



BEA WebLogic Platform™

7.0 Supported Configurations: Sun Solaris 8 on SPARC

Copyright

Copyright © 2006 BEA Systems, Inc. All Rights Reserved.

Restricted Rights Legend

This software and documentation is subject to and made available only pursuant to the terms of the BEA Systems License Agreement and may be used or copied only in accordance with the terms of that agreement. It is against the law to copy the software except as specifically allowed in the agreement. This document may not, in whole or in part, be copied, photocopied, reproduced, translated, or reduced to any electronic medium or machine readable form without prior consent, in writing, from BEA Systems, Inc.

Use, duplication or disclosure by the U.S. Government is subject to restrictions set forth in the BEA Systems License Agreement and in subparagraph (c)(1) of the Commercial Computer Software-Restricted Rights Clause at FAR 52.227-19; subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.227-7013, subparagraph (d) of the Commercial Computer Software--Licensing clause at NASA FAR supplement 16-52.227-86; or their equivalent.

Information in this document is subject to change without notice and does not represent a commitment on the part of BEA Systems. THE SOFTWARE AND DOCUMENTATION ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND INCLUDING WITHOUT LIMITATION, ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. FURTHER, BEA Systems DOES NOT WARRANT, GUARANTEE, OR MAKE ANY REPRESENTATIONS REGARDING THE USE, OR THE RESULTS OF THE USE, OF THE SOFTWARE OR WRITTEN MATERIAL IN TERMS OF CORRECTNESS, ACCURACY, RELIABILITY, OR OTHERWISE.

Trademarks or Service Marks

BEA, BEA Liquid Data for WebLogic, BEA WebLogic Server, Built on BEA, Jolt, JoltBeans, SteelThread, Top End, Tuxedo, and WebLogic are registered trademarks of BEA Systems, Inc. BEA Builder, BEA Campaign Manager for WebLogic, BEA eLink, BEA Manager, BEA MessageQ, BEA WebLogic Commerce Server, BEA WebLogic Enterprise, BEA WebLogic Enterprise Platform, BEA WebLogic Enterprise Security, BEA WebLogic Express, BEA WebLogic Integration, BEA WebLogic Java Adapter for Mainframe, BEA WebLogic JDriver, BEA WebLogic JRockit, BEA WebLogic Log Central, BEA WebLogic Personalization Server, BEA WebLogic Platform, BEA WebLogic Portal, BEA WebLogic Server Process Edition, BEA WebLogic WorkGroup Edition, BEA WebLogic Workshop, and Liquid Computing are trademarks of BEA Systems, Inc. BEA Mission Critical Support is a service mark of BEA Systems, Inc. All other company and product names may be the subject of intellectual property rights reserved by third parties.

All other trademarks are the property of their respective companies.

Contents

1. Sun Solaris 8 on SPARC with 7.0 SP7	
Configuration Requirements	1-2
Known Issues	1-3
2. Sun Solaris 8 on SPARC with 7.0 SP6	
Configuration Requirements	2-2
Known Issues	2-3
3. Sun Solaris 8 on SPARC with 7.0 SP5	
Configuration Requirements	3-2
Known Issues	3-3
4. Sun Solaris 8 on SPARC with 7.0 SP4	
Configuration Requirements	4-2
Known Issues	4-3
5. Sun Solaris 8 on SPARC with WebLogic Server 7.0 SP3	
Configuration Requirements	5-2
Known Issues	5-3
6. Sun Solaris 8 on SPARC with 7.0 SP2	
Configuration Requirements	6-2
Known Issues	6-3
7. Sun Solaris 8 on SPARC with 7.0 SP1	
Configuration Requirements	7-2
Known Issues	7-3

8. Sun Solaris 8 on SPARC with WebLogic Platform 7.0

Configuration Requirements8-2

Known Issues8-3

Sun Solaris 8 on SPARC with 7.0 SP7

Product Components Supported on this Configuration

	WebLogic Server	WebLogic Workshop	WebLogic Integration	WebLogic Portal
Run-time	✓	✓	✓	✓
Design/Dev Tools*	✓	✗	✗	✗

* For design and development tools support, see the “Configuration Requirements” section below.

✓ Supported

✗ Not supported

This section provides the following information:

- [Configuration Requirements](#)
- [Known Issues](#)

Related Information

- For information about supported database configurations, Web servers, and browsers, plus support for interoperability tools and WebLogic Platform product support information, see [WebLogic Platform 7.0 Supported Configurations](#).
- For details about Sun Solaris 8, visit Sun’s Solaris Web page at: <http://www.sun.com/software/solaris>.
- For Sun’s support services information site, see <http://www.sun.com/service/warrantiescontracts>. If you have a support contract for the use of Solaris platforms, you may be able to obtain support for general Java issues (for example, JVM problems).

- You can run WebLogic software on Solaris using the SDK available from Sun Microsystems at: <http://java.sun.com/products/?frontpage-main>. BEA recommends using the latest available versions of the JVMs supported by BEA, except where noted otherwise in our *Supported Configurations* document.

Configuration Requirements

Table 1-1 Requirements for 7.0 SP7 on Sun Solaris 8 on SPARC

Operating System Version and Patches	Solaris 8
Chip Architecture and Minimum Processor Speed	UltraSPARC (168 MHz)
SDK	<div><div>Sun Java 2 SDK 1.4.2_10 and all later service packs of 1.4.2 with the Java HotSpot™ Client and Server VMs (32-bit)</div><div><ul style="list-style-type: none">• Supports the Java HotSpot™ Client and Server VMs.• WebLogic Integration and WebLogic Portal are configured to use the Sun Java 2 SDK 1.4.2_10 with the Java HotSpot Server VM. For details, see “Using the HotSpot Virtual Machine” in “Performance Tuning” in “System Administration” in the <i>WebLogic Portal Administration Guide</i> at the following URL: http://e-docs.bea.com/wlp/docs70/admin/sysadmin.htm</div></div>
Design and Development Tools	<div>Supports WebLogic Server development tools.</div> <div>For more information about WebLogic Platform design and development tools support, see “Supported Configurations for Design and Development Tools in Version 7.0 SP7” in <i>Supported Configurations for WebLogic Platform 7.0</i>.</div>
RAM	512 MB required; 1 GB recommended
Disk Space	For any components of WebLogic Platform or for the full WebLogic Platform product, see Disk Space Requirements .
Performance Pack	Included

Table 1-1 Requirements for 7.0 SP7 on Sun Solaris 8 on SPARC (Continued)

Node Manager	Java	
BEA jDrivers for Oracle	Oracle 9.2.0	<div>The following shared libraries are provided:<ul style="list-style-type: none">lib/solaris/oci920_8/libweblogicoci38.solib/solaris/oci920_8/libweblogicoxa38.so</div>

Known Issues

For more information about known issues with any components of this release, see the appropriate *Release Notes* document. For a complete list of *Release Notes* supporting WebLogic Platform 7.0, see:

<http://e-docs.bea.com/platform/docs70/interm/relnotes.html>

Sun Solaris 8 on SPARC with 7.0 SP7

Sun Solaris 8 on SPARC with 7.0 SP6

Product Components Supported on this Configuration

	WebLogic Server	WebLogic Workshop	WebLogic Integration	WebLogic Portal
Run-time	✓	✓	✓	✓
Design/Dev Tools*	✓	✗	✗	✗

* For design and development tools support, see the “Configuration Requirements” section below.

✓ Supported

✗ Not supported

This section provides the following information:

- [Configuration Requirements](#)
- [Known Issues](#)

Related Information

- For information about supported database configurations, Web servers, and browsers, plus support for interoperability tools and WebLogic Platform product support information, see [WebLogic Platform 7.0 Supported Configurations](#).
- For details about Sun Solaris 8, visit Sun’s Solaris Web page at: <http://www.sun.com/software/solaris>.
- For Sun’s support services information site, see <http://www.sun.com/service/warrantiescontracts>. If you have a support contract for the use of Solaris platforms, you may be able to obtain support for general Java issues (for example, JVM problems).

- You can run WebLogic software on Solaris using the SDK available from Sun Microsystems at: <http://java.sun.com/products/?frontpage-main>. BEA recommends using the latest available versions of the JVMs supported by BEA, except where noted otherwise in our *Supported Configurations* document.

Configuration Requirements

Table 2-1 Requirements for 7.0 SP6 on Sun Solaris 8 on SPARC

Operating System Version and Patches	Solaris 8
Chip Architecture and Minimum Processor Speed	UltraSPARC (168 MHz)
SDK	<div><div>Fully-supported</div><div><div>Sun Java 2 SDK 1.3.1_14 (32-bit) and all later service packs of 1.3.1</div><div><ul style="list-style-type: none">• Supports the Java HotSpot™ Client and Server VMs.• WebLogic Integration and WebLogic Portal are configured to use the Sun Java 2 SDK 1.3.1_14 with the Java HotSpot Server VM. For details, see “Using the HotSpot Virtual Machine” in “Performance Tuning” in “System Administration” in the <i>WebLogic Portal Administration Guide</i> at the following URL: http://e-docs.bea.com/wlp/docs70/admin/sysadmin.htm</div></div></div> <div><div>Client-only</div><div><div>Sun Java 2 SDK 1.4.2_06 (32-bit) with Java HotSpot™ Client VM and all later service packs of 1.4.2</div><div><ul style="list-style-type: none">• Supported only for WebLogic Server clients and the WebLogic Workshop IDE. Can be used to run WebLogic Server RMI or Web Services clients that remotely connect to a server running in a separate VM.• It is not supported by WebLogic Portal or WebLogic Integration clients and development tools. Is is also not supported by running server instances of WebLogic Server or other WebLogic Platform components.</div></div></div>

Table 2-1 Requirements for 7.0 SP6 on Sun Solaris 8 on SPARC (Continued)

Design and Development Tools	Supports WebLogic Server development tools. For more information about WebLogic Platform design and development tools support, see “Supported Configurations for Design and Development Tools in Version 7.0 SP6” in <i>Supported Configurations for WebLogic Platform 7.0</i> .	
RAM	512 MB required; 1 GB recommended	
Disk Space	For any components of WebLogic Platform or for the full WebLogic Platform product, see Disk Space Requirements .	
Performance Pack	Included	
Node Manager	Java	
BEA jDrivers for Oracle	For this Oracle client version:	The following shared libraries are provided:
	Oracle 8.1.7	<ul style="list-style-type: none"> lib/solaris/oci817_8/libweblogicoci38.so lib/solaris/oci817_8/libweblogicoxa38.so
	Oracle 9.2.0	<ul style="list-style-type: none"> lib/solaris/oci920_8/libweblogicoci38.so lib/solaris/oci920_8/libweblogicoxa38.so

Known Issues

- The JIT (Just-In-Time) Compiler is supported only for 1.2.2_05a when the `export _JVM_ARGS="inline_instrs_jit=0"` directive is being used. This is due to two Sun bugs: #4333396 (JVM crash during JIT) and #4333696. The error message reads:


```
SIGABRT and JIT coredump: panic: Unexpected operand kind(10) in j86OpndImage.
```

 These bugs also affect 1.2.1_04, so you must Disable aggressive inlining by the JIT with:

```
export _JIT_ARGS=novinline.
```
- 7.3.4 jDriver for Oracle is not supported with JDK 1.3.1.
- Some Solaris JVMs report an incorrect IP number. The IP number reported for the machine is the first number in the `/etc/hosts` file. Unfortunately, this number is frequently `127.0.0.1`, the standard loopback network address for the machine. This problem affects licenses granted for specific IP numbers. We have also observed this

problem in a cluster where an HTTP request is passed by a Web server or another WebLogic Server via the `HttpClusterServlet`, to a WebLogic Server running on a Solaris machine with this configuration problem. The `127.0.0.1` IP number is carried with the server's response. Subsequent calls to that machine time out because the IP number is incorrect.

To determine whether you have this problem on your Solaris computer, run the following command:

```
java utils.netAddresses
```

If you see `127.0.0.1` in the output, ask the system administrator to move the computer's network IP address to the beginning of the `/etc/hosts` file.

- For information about suggested values for some Solaris TCP and VM-related tunable parameters, see “[Operating System Tuning](#)” in *BEA WebLogic Server 7.0 Performance and Tuning*.

For more information about known issues with any components of this release, see the appropriate *Release Notes* document. For a complete list of *Release Notes* supporting WebLogic Platform 7.0, see:

<http://e-docs.bea.com/platform/docs70/interm/relnotes.html>

Sun Solaris 8 on SPARC with 7.0 SP5

Product Components Supported on this Configuration

	WebLogic Server	WebLogic Workshop	WebLogic Integration	WebLogic Portal
Run-time	✓	✓	✓	✓
Design/Dev Tools*	✓	✗	✗	✗

* For design and development tools support, see the “Configuration Requirements” section below.

✓ Supported
✗ Not supported

This section provides the following information:

- [Configuration Requirements](#)
- [Known Issues](#)

Related Information

- For information about supported database configurations, Web servers, and browsers, plus support for interoperability tools and WebLogic Platform product support information, see [WebLogic Platform 7.0 Supported Configurations](#).
- For details about Sun Solaris 8, visit Sun’s Solaris Web page at: <http://www.sun.com/solaris>.
- For Sun’s support services information site, see <http://www.sun.com/service/support>. If you have a support contract for the use of Solaris platforms, you may be able to obtain support for general Java issues (for example, JVM problems).

- You can run WebLogic software on Solaris using the SDK available from Sun Microsystems at: <http://java.sun.com/products/?frontpage-main>. BEA recommends using the latest available versions of the JVMs supported by BEA, except where noted otherwise in our *Supported Configurations* document.

Configuration Requirements

Table 3-1 Requirements for 7.0 SP5 on Sun Solaris 8 on SPARC

Operating System Version and Patches	Solaris 8
Chip Architecture and Minimum Processor Speed	UltraSPARC (168 MHz)
SDK	<div><div>Fully-supported</div><div><div>Sun Java 2 SDK 1.3.1_10 (32 bit) and all later service packs of 1.3.1</div><div><ul style="list-style-type: none">• Supports the Java HotSpot™ Client and Server VMs.• WebLogic Integration and WebLogic Portal are configured to use the Sun Java 2 SDK 1.3.1_10 with the Java HotSpot Server VM. For details, see “Using the HotSpot Virtual Machine” in “Performance Tuning” in “System Administration” in the <i>WebLogic Portal Administration Guide</i> at the following URL: http://e-docs.bea.com/wlp/docs70/admin/sysadmin.htm</div></div></div> <div><div>Client-only</div><div><div>Sun Java 2 SDK 1.4.2_03 (32-bit) with Java HotSpot™ Client VM and all later service packs of 1.4.2</div><div><ul style="list-style-type: none">• Supported only for WebLogic Server clients and the WebLogic Workshop IDE. Can be used to run WebLogic Server RMI or Web Services clients that remotely connect to a server running in a separate VM.• It is not supported by WebLogic Portal or WebLogic Integration clients and development tools. Is is also not supported by running server instances of WebLogic Server or other WebLogic Platform components.</div></div></div>

Table 3-1 Requirements for 7.0 SP5 on Sun Solaris 8 on SPARC (Continued)

Design and Development Tools	Supports WebLogic Server development tools. For more information about WebLogic Platform design and development tools support, see “Supported Configurations for Design and Development Tools in Version 7.0 SP5” in <i>Supported Configurations for WebLogic Platform 7.0</i> .	
RAM	512 MB required; 1 GB recommended	
Disk Space	For any components of WebLogic Platform or for the full WebLogic Platform product, see Disk Space Requirements .	
Performance Pack	Included	
Node Manager	Java	
BEA jDrivers for Oracle	For this Oracle client version:	The following shared libraries are provided:
	Oracle 8.1.7	<ul style="list-style-type: none"> lib/solaris/oci817_8/libweblogicoci38.so lib/solaris/oci817_8/libweblogicoxa38.so
	Oracle 9.0.1	<ul style="list-style-type: none"> lib/solaris/oci901_8/libweblogicoci38.so lib/solaris/oci901_8/libweblogicoxa38.so
	Oracle 9.2.0	<ul style="list-style-type: none"> lib/solaris/oci920_8/libweblogicoci38.so lib/solaris/oci920_8/libweblogicoxa38.so

Known Issues

- The JIT (Just-In-Time) Compiler is supported only for 1.2.2_05a when the `export _JVM_ARGS="inline_instrs_jit=0"` directive is being used. This is due to two Sun bugs: #4333396 (JVM crash during JIT) and #4333696. The error message reads:

```
SIGABRT and JIT coredump: panic: Unexpected operand kind(10) in
j86OpndImage.
```

These bugs also affect 1.2.1_04, so you must Disable aggressive inlining by the JIT with:
`export _JIT_ARGS= novinline.`

- 7.3.4 jDriver for Oracle is not supported with JDK 1.3.1.

- Some Solaris JVMs report an incorrect IP number. The IP number reported for the machine is the first number in the `/etc/hosts` file. Unfortunately, this number is frequently `127.0.0.1`, the standard loopback network address for the machine. This problem affects licenses granted for specific IP numbers. We have also observed this problem in a cluster where an HTTP request is passed by a Web server or another WebLogic Server via the `HttpClusterServlet`, to a WebLogic Server running on a Solaris machine with this configuration problem. The `127.0.0.1` IP number is carried with the server's response. Subsequent calls to that machine time out because the IP number is incorrect.

To determine whether you have this problem on your Solaris computer, run the following command:

```
java utils.netAddresses
```

If you see `127.0.0.1` in the output, ask the system administrator to move the computer's network IP address to the beginning of the `/etc/hosts` file.

- If you have problems with `OutOfMemory` errors and the JVM crashing with JDK 1.3, try setting: `-XX:MaxPermSize=128m`. For WebLogic Integration, use the following setting: `-XX:MaxPermSize=256m`.
- For information about suggested values for some Solaris TCP and VM-related tunable parameters, see “[Operating System Tuning](#)” in *BEA WebLogic Server 7.0 Performance and Tuning*.

For more information about known issues with any components of this release, see the appropriate *Release Notes* document. For a complete list of *Release Notes* supporting WebLogic Platform 7.0, see:

<http://e-docs.bea.com/platform/docs70/interm/relnotes.html>

Sun Solaris 8 on SPARC with 7.0 SP4

Product Components Supported on this Configuration

	WebLogic Server	WebLogic Workshop	WebLogic Integration	WebLogic Portal
Run-time	✓	✓	✓	✓
Design/Dev Tools*	✓	✗	✗	✗

* For design and development tools support, see the “Configuration Requirements” section below.

✓ Supported

✗ Not supported

This section provides the following information:

- [Configuration Requirements](#)
- [Known Issues](#)

Related Information

- For information about supported database configurations, Web servers, and browsers, plus support for interoperability tools and WebLogic Platform product support information, see [WebLogic Platform 7.0 Supported Configurations](#).
- For details about Sun Solaris 8, visit Sun’s Solaris Web page at: <http://www.sun.com/solaris>.
- For Sun’s support services information site, see <http://www.sun.com/service/support>. If you have a support contract for the use of Solaris platforms, you may be able to obtain support for general Java issues (for example, JVM problems).

- You can run WebLogic software on Solaris using the SDK available from Sun Microsystems at: <http://java.sun.com/products/?frontpage-main>. BEA recommends using the latest available versions of the JVMs supported by BEA, except where noted otherwise in our *Supported Configurations* document.

Configuration Requirements

Table 4-1 Requirements for 7.0 SP4 on Sun Solaris 8 on SPARC

Operating System Version and Patches	Solaris 8
Chip Architecture and Minimum Processor Speed	UltraSPARC (168 MHz)
SDK	<div><div>Fully-supported</div><div><div>Sun Java 2 SDK 1.3.1_08 (32-bit) and all later service packs of 1.3.1</div><div><ul style="list-style-type: none">• Supports the Java HotSpot™ Client and Server VMs• WebLogic Integration and WebLogic Portal are configured to use the Sun Java 2 SDK 1.3.1_08 with the Java HotSpot Server VM. For details, see “Using the HotSpot Virtual Machine” in “Performance Tuning” in “System Administration” in the <i>WebLogic Portal Administration Guide</i> at the following URL: http://e-docs.bea.com/wlp/docs70/admin/ysadmin.htm</div></div></div> <div><div>Client-only</div><div><div>Sun Java 2 SDK 1.4.1_02 (32-bit) with Java HotSpot™ Client VM and all later service packs of 1.4.1</div><div><ul style="list-style-type: none">• Supported only for WebLogic Server clients and the WebLogic Workshop IDE. Can be used to run WebLogic Server RMI or Web Services clients that remotely connect to a server running in a separate VM.• It is not supported by WebLogic Portal or WebLogic Integration clients and development tools. Is is also not supported by running server instances of WebLogic Server or other WebLogic Platform components.</div></div></div>

Table 4-1 Requirements for 7.0 SP4 on Sun Solaris 8 on SPARC (Continued)

Design and Development Tools	Supports WebLogic Server development tools. For more information about WebLogic Platform design and development tools support, see “Supported Configurations for Design and Development Tools in Version 7.0 SP4” in <i>Supported Configurations for WebLogic Platform 7.0</i> .	
RAM	512 MB required; 1 GB recommended	
Disk Space	For any components of WebLogic Platform or for the full WebLogic Platform product, see Disk Space Requirements .	
Performance Pack	Included	
Node Manager	Java	
BEA jDrivers for Oracle	For this Oracle client version:	The following shared libraries are provided:
	Oracle 8.1.7	<ul style="list-style-type: none"> lib/solaris/oci817_8/libweblogicoci38.so lib/solaris/oci817_8/libweblogicoxa38.so
	Oracle 9.0.1	<ul style="list-style-type: none"> lib/solaris/oci901_8/libweblogicoci38.so lib/solaris/oci901_8/libweblogicoxa38.so
	Oracle 9.2.0	<ul style="list-style-type: none"> lib/solaris/oci920_8/libweblogicoci38.so lib/solaris/oci920_8/libweblogicoxa38.so

Known Issues

- The JIT (Just-In-Time) Compiler is supported only for 1.2.2_05a when the export `_JVM_ARGS="inline_instrs_jit=0"` directive is being used. This is due to two Sun bugs: #4333396 (JVM crash during JIT) and #4333696. The error message reads:

```
SIGABRT and JIT coredump: panic: Unexpected operand kind(10) in
j86OpndImage.
```

These bugs also affect 1.2.1_04, so you must Disable aggressive inlining by the JIT with:
export `_JIT_ARGS=novinline`.

- 7.3.4 jDriver for Oracle is not supported with JDK 1.3.1.

- Some Solaris JVMs report an incorrect IP number. The IP number reported for the machine is the first number in the `/etc/hosts` file. Unfortunately, this number is frequently `127.0.0.1`, the standard loopback network address for the machine. This problem affects licenses granted for specific IP numbers. We have also observed this problem in a cluster where an HTTP request is passed by a Web server or another WebLogic Server via the `HttpClusterServlet`, to a WebLogic Server running on a Solaris machine with this configuration problem. The `127.0.0.1` IP number is carried with the server's response. Subsequent calls to that machine time out because the IP number is incorrect.

To determine whether you have this problem on your Solaris computer, run the following command:

```
java utils.netAddresses
```

If you see `127.0.0.1` in the output, ask the system administrator to move the computer's network IP address to the beginning of the `/etc/hosts` file.

- If you have problems with `OutOfMemory` errors and the JVM crashing with JDK 1.3, try setting: `-XX:MaxPermSize=128m`. For WebLogic Integration, use the following setting: `-XX:MaxPermSize=256m`.
- For information about suggested values for some Solaris TCP and VM-related tunable parameters, see “[Operating System Tuning](#)” in *BEA WebLogic Server 7.0 Performance and Tuning*.

For more information about known issues with any components of this release, see the appropriate *Release Notes* document. For a complete list of *Release Notes* supporting WebLogic Platform 7.0, see:

<http://e-docs.bea.com/platform/docs70/interm/relnotes.html>

Sun Solaris 8 on SPARC with WebLogic Server 7.0 SP3

Product Components Supported on this Configuration

	WebLogic Server	WebLogic Workshop	WebLogic Integration	WebLogic Portal
Run-time	✓	✓	✗	✗
Design/Dev Tools*	✓	✗	✗	✗

* For design and development tools support, see the “Configuration Requirements” section below.

✓ Supported
✗ Not supported

This section provides the following information:

- [Configuration Requirements](#)
- [Known Issues](#)

Related Information

- For information about supported database configurations, Web servers, and browsers, plus support for interoperability tools and WebLogic Platform product support information, see [WebLogic Platform 7.0 Supported Configurations](#).
- For details about Sun Solaris 8, visit Sun’s Solaris Web page at: <http://www.sun.com/solaris>.
- For Sun’s support services information site, see <http://www.sun.com/service/support>. If you have a support contract for the use of Solaris platforms, you may be able to obtain support for general Java issues (for example, JVM problems).

- You can run WebLogic software on Solaris using the SDK available from Sun Microsystems at: <http://java.sun.com/products/?frontpage-main>. BEA recommends using the latest available versions of the JVMs supported by BEA, except where noted otherwise in our *Supported Configurations* document.

Configuration Requirements

Table 5-1 Requirements for 7.0 SP3 on Sun Solaris 8 on SPARC

Operating System Version and Patches	Solaris 8
Chip Architecture and Minimum Processor Speed	UltraSPARC (168 MHz)
SDK	Fully-supported
	Sun Java 2 SDK 1.3.1_08 (32-bit) and all later service packs of 1.3.1
	Supports the Java HotSpot™ Client and Server VMs
	Client-only
	Sun Java 2 SDK 1.4.1_02 (32-bit) with Java HotSpot™ Client VM and all later service packs of 1.4.1
	<ul style="list-style-type: none">• Supported only for WebLogic Server clients and the WebLogic Workshop IDE. Can be used to run WebLogic Server RMI or Web Services clients that remotely connect to a server running in a separate VM.• It is not supported by WebLogic Portal or WebLogic Integration clients and development tools. Is also not supported by running server instances of WebLogic Server or other WebLogic Platform components.
Design and Development Tools	Supports WebLogic Server development tools.
RAM	512 MB required; 1 GB recommended
Disk Space	For any components of WebLogic Platform or for the full WebLogic Platform product, see Disk Space Requirements .

Table 5-1 Requirements for 7.0 SP3 on Sun Solaris 8 on SPARC

Performance Pack	Included	
Node Manager	Java	
BEA jDrivers for Oracle	For this Oracle client version:	The following shared libraries are provided:
	Oracle 8.1.7	<ul style="list-style-type: none"> lib/solaris/oci817_8/libweblogicoci38.so lib/solaris/oci817_8/libweblogicoxa38.so
	Oracle 9.0.1	<ul style="list-style-type: none"> lib/solaris/oci901_8/libweblogicoci38.so lib/solaris/oci901_8/libweblogicoxa38.so
	Oracle 9.2.0	<ul style="list-style-type: none"> lib/solaris/oci920_8/libweblogicoci38.so lib/solaris/oci920_8/libweblogicoxa38.so

Known Issues

- The JIT (Just-In-Time) Compiler is supported only for 1.2.2_05a when the `export _JVM_ARGS="inline_instrs_jit=0"` directive is being used. This is due to two Sun bugs: #4333396 (JVM crash during JIT) and #4333696. The error message reads:


```
SIGABRT and JIT coredump: panic: Unexpected operand kind(10) in
j86OpndImage.
```

These bugs also affect 1.2.1_04, so you must Disable aggressive inlining by the JIT with:
`export _JIT_ARGS=novinline.`
- 7.3.4 jDriver for Oracle is not supported with JDK 1.3.1.
- Some Solaris JVMs report an incorrect IP number. The IP number reported for the machine is the first number in the `/etc/hosts` file. Unfortunately, this number is frequently `127.0.0.1`, the standard loopback network address for the machine. This problem affects licenses granted for specific IP numbers. We have also observed this problem in a cluster where an HTTP request is passed by a Web server or another WebLogic Server via the `HttpClusterServlet`, to a WebLogic Server running on a Solaris machine with this configuration problem. The `127.0.0.1` IP number is carried with the server's response. Subsequent calls to that machine time out because the IP number is incorrect.

To determine whether you have this problem on your Solaris computer, run the following command:

```
java utils.netAddresses
```

If you see 127.0.0.1 in the output, ask the system administrator to move the computer's network IP address to the beginning of the `/etc/hosts` file.

- If you have problems with OutOfMemory errors and the JVM crashing with JDK 1.3, try setting: `-XX:MaxPermSize=128m`. For WebLogic Integration, use the following setting: `-XX:MaxPermSize=256m`.
- For information about suggested values for some Solaris TCP and VM-related tunable parameters, see “[Operating System Tuning](#)” in *BEA WebLogic Server 7.0 Performance and Tuning*.

For more information about known issues with any components of this release, see the appropriate *Release Notes* document. For a complete list of *Release Notes* supporting WebLogic Platform 7.0, see:

<http://e-docs.bea.com/platform/docs70/interm/relnotes.html>

Sun Solaris 8 on SPARC with 7.0 SP2

Product Components Supported on this Configuration

	WebLogic Server	WebLogic Workshop	WebLogic Integration	WebLogic Portal
Run-time	✓	✓	✓	✓
Design/Dev Tools*	✓	✗	✗	✗

* For design and development tools support, see the “Configuration Requirements” section below.

✓ Supported
✗ Not supported

This section provides the following information:

- [Configuration Requirements](#)
- [Known Issues](#)

Related Information

- For information about supported database configurations, Web servers, and browsers, plus support for interoperability tools and WebLogic Platform product support information, see [WebLogic Platform 7.0 Supported Configurations](#).
- For details about Sun Solaris 8, visit Sun’s Solaris Web page at: <http://www.sun.com/solaris>.
- For Sun’s support services information site, see <http://www.sun.com/service/support>. If you have a support contract for the use of Solaris platforms, you may be able to obtain support for general Java issues (for example, JVM problems).

- You can run WebLogic software on Solaris using the SDK available from Sun Microsystems at: <http://java.sun.com/products/?frontpage-main>. BEA recommends using the latest available versions of the JVMs supported by BEA, except where noted otherwise in our *Supported Configurations* document.

Configuration Requirements

Table 6-1 Requirements for 7.0 SP2 on Sun Solaris 8 on SPARC

Operating System Version and Patches	Solaris 8
Chip Architecture and Minimum Processor Speed	UltraSPARC (168 MHz)
SDK	<div><div>Fully-supported</div><div><div>Sun Java 2 SDK 1.3.1_06 (32-bit) and all later service packs of 1.3.1</div><div><ul style="list-style-type: none">• Supports the Java HotSpot™ Client and Server VMs• WebLogic Integration and WebLogic Portal are configured to use the Sun Java 2 SDK 1.3.1_06 with the Java HotSpot Server VM. For details, see “Using the HotSpot Virtual Machine” in “Performance Tuning” in “System Administration” in the <i>WebLogic Portal Administration Guide</i> at the following URL: http://e-docs.bea.com/wlp/docs70/admin/sysadmin.htm</div></div></div> <div><div>Client JVM</div><div><div>Sun Java 2 SDK 1.4.1 (32-bit) with Java HotSpot™ Client VM and all later service packs of Sun Java 2 SDK 1.4.1</div><div><ul style="list-style-type: none">• Supported only for WebLogic Server clients and the WebLogic Workshop IDE. Can be used to run WebLogic Server RMI or Web Services clients that remotely connect to a server running in a separate VM.• It is not supported by WebLogic Portal or WebLogic Integration clients and development tools. Is is also not supported by running server instances of WebLogic Server or other WebLogic Platform components.</div></div></div>

Table 6-1 Requirements for 7.0 SP2 on Sun Solaris 8 on SPARC (Continued)

Design and Development Tools	Supports WebLogic Server development tools. For more information about WebLogic Platform design and development tools support, see “Supported Configurations for Design and Development Tools in Version 7.0 SP2” in <i>Supported Configurations for WebLogic Platform 7.0</i> .	
RAM	512 MB required; 1 GB recommended	
Disk Space	For any components of WebLogic Platform or for the full WebLogic Platform product, see Disk Space Requirements .	
Performance Pack	Included	
Node Manager	Java	
BEA jDrivers for Oracle	For this Oracle client version:	The following shared libraries are provided:
	Oracle 8.1.7	<ul style="list-style-type: none"> lib/solaris/oci817_8/libweblogicoci38.so lib/solaris/oci817_8/libweblogicoxa38.so
	Oracle 9.0.1	<ul style="list-style-type: none"> lib/solaris/oci901_8/libweblogicoci38.so lib/solaris/oci901_8/libweblogicoxa38.so
	Oracle 9.2.0	<ul style="list-style-type: none"> lib/solaris/oci920_8/libweblogicoci38.so lib/solaris/oci920_8/libweblogicoxa38.so

Known Issues

- The JIT (Just-In-Time) Compiler is supported only for 1.2.2_05a when the export `_JVM_ARGS="inline_instrs_jit=0"` directive is being used. This is due to two Sun bugs: #4333396 (JVM crash during JIT) and #4333696. The error message reads:


```
SIGABRT and JIT coredump: panic: Unexpected operand kind(10) in j86OpndImage.
```

These bugs also affect 1.2.1_04, so you must Disable aggressive inlining by the JIT with:
`export _JIT_ARGS=novinline.`
- 7.3.4 jDriver for Oracle is not supported with JDK 1.3.1.

- Some Solaris JVMs report an incorrect IP number. The IP number reported for the machine is the first number in the `/etc/hosts` file. Unfortunately, this number is frequently `127.0.0.1`, the standard loopback network address for the machine. This problem affects licenses granted for specific IP numbers. We have also observed this problem in a cluster where an HTTP request is passed by a Web server or another WebLogic Server via the `HttpClusterServlet`, to a WebLogic Server running on a Solaris machine with this configuration problem. The `127.0.0.1` IP number is carried with the server's response. Subsequent calls to that machine time out because the IP number is incorrect.

To determine whether you have this problem on your Solaris computer, run the following command:

```
java utils.netAddresses
```

If you see `127.0.0.1` in the output, ask the system administrator to move the computer's network IP address to the beginning of the `/etc/hosts` file.

- If you have problems with `OutOfMemory` errors and the JVM crashing with JDK 1.3, try setting: `-XX:MaxPermSize=128m`. For WebLogic Integration, use the following setting: `-XX:MaxPermSize=256m`.
- For information about suggested values for some Solaris TCP and VM-related tunable parameters, see “[Operating System Tuning](#)” in *BEA WebLogic Server 7.0 Performance and Tuning*.

For more information about known issues with any components of this release, see the appropriate *Release Notes* document. For a complete list of *Release Notes* supporting WebLogic Platform 7.0, see:

<http://e-docs.bea.com/platform/docs70/interm/relnotes.html>

Sun Solaris 8 on SPARC with 7.0 SP1

Product Components Supported on this Configuration

	WebLogic Server	WebLogic Workshop	WebLogic Integration	WebLogic Portal
Run-time	✓	✓	✓	✓
Design/Dev Tools*	✓	✗	✗	✗

* For design and development tools support, see the “Configuration Requirements” section below.

✓ Supported

✗ Not supported

This section provides the following information:

- [Configuration Requirements](#)
- [Known Issues](#)

Related Information

- For information about supported database configurations, Web servers, and browsers, plus support for interoperability tools and WebLogic Platform product support information, see [WebLogic Platform 7.0 Supported Configurations](#).
- For details about Sun Solaris 8, visit Sun’s Solaris Web page at: <http://www.sun.com/solaris>.
- For Sun’s support services information site, see <http://www.sun.com/service/support>. If you have a support contract for the use of Solaris platforms, you may be able to obtain support for general Java issues (for example, JVM problems).

- You can run WebLogic software on Solaris using the SDK available from Sun Microsystems at: <http://java.sun.com/products/?frontpage-main>. BEA recommends using the latest available versions of the JVMs supported by BEA, except where noted otherwise in our *Supported Configurations* document.

Configuration Requirements

Table 7-1 Requirements for 7.0 SP1 on Sun Solaris 8 on SPARC

Operating System Version and Patches	Solaris 8	If you are planning to use the Sun Java 2 SDK 1.3.1_03 with the Solaris operating system, you must install the latest Sun Java 2 SDK 1.3.1_03 patches. For additional information, see: http://java.sun.com/j2se/1.3/install-solaris-patches.html
Chip Architecture and Minimum Processor Speed	UltraSparc (168 MHz)	
SDK	Sun Java 2 SDK 1.3.1_03 (32 bit) and all later service packs of 1.3.1	<ul style="list-style-type: none">• Bundled with WebLogic Platform 7.0 SP1 and installed, automatically, under the BEA Home directory.• Supports the Java HotSpot™ Client and Server VMs.• WebLogic Integration and WebLogic Portal are configured to use the Sun Java 2 SDK 1.3.1 with the Java HotSpot Server VM. For additional information, see “Using the HotSpot Virtual Machine” in “Performance Tuning” in “System Administration” in the <i>WebLogic Portal Administration Guide</i>, which is available at the following URL: http://e-docs.bea.com/wlp/docs70/admin/sysadmin.htm
	Sun Java 2 SDK 1.3.1_04	Supported on WebLogic Server and WebLogic Portal only.
	Sun Java 2 SDK 1.3.1_06	Supported on WebLogic Server only.
Design and Development Tools	Supports WebLogic Server development tools. For more information about WebLogic Platform design and development tools support, see “Supported Configurations for Design and Development Tools in Version 7.0 SP1” in <i>Supported Configurations for WebLogic Platform 7.0</i> .	
RAM	512 MB required; 1 GB recommended	

Table 7-1 Requirements for 7.0 SP1 on Sun Solaris 8 on SPARC (Continued)

Disk Space	For any components of WebLogic Platform or for the full WebLogic Platform product, see Disk Space Requirements .	
Performance Pack	Included	
Node Manager	Java	
BEA jDrivers for Oracle	For this Oracle client version:	The following shared libraries are provided:
	Oracle 8.1.7	<ul style="list-style-type: none"> lib/solaris/oci817_8/libweblogicoci38.so lib/solaris/oci817_8/libweblogicoxa38.so
	Oracle 9.0.1	<ul style="list-style-type: none"> lib/solaris/oci901_8/libweblogicoci38.so lib/solaris/oci901_8/libweblogicoxa38.so
	Oracle 9.2.0 (Requires Sun Java 2 SDK 1.3.1_04 and higher)	<ul style="list-style-type: none"> lib/solaris/oci920_8/libweblogicoci38.so lib/solaris/oci920_8/libweblogicoxa38.so

Known Issues

- The JIT (Just-In-Time) Compiler is supported only for 1.2.2_05a when the `export _JVM_ARGS="inline_instrs_jit=0"` directive is being used. This is due to two Sun bugs: #4333396 (JVM crash during JIT) and #4333696. The error message reads:

```
SIGABRT and JIT coredump: panic: Unexpected operand kind(10) in
j86OpndImage.
```

These bugs also affect 1.2.1_04, so you must Disable aggressive inlining by the JIT with:
`export _JIT_ARGS=nowinline.`

- 7.3.4 jDriver for Oracle is not supported with JDK 1.3.1.
- Some Solaris JVMs report an incorrect IP number. The IP number reported for the machine is the first number in the `/etc/hosts` file. Unfortunately, this number is frequently `127.0.0.1`, the standard loopback network address for the machine. This problem affects licenses granted for specific IP numbers. We have also observed this problem in a cluster where an HTTP request is passed by a Web server or another WebLogic Server via the `HttpClusterServlet`, to a WebLogic Server running on a Solaris machine with this configuration problem. The `127.0.0.1` IP number is carried with the

server's response. Subsequent calls to that machine time out because the IP number is incorrect.

To determine whether you have this problem on your Solaris computer, run the following command:

```
java utils.netAddresses
```

If you see `127.0.0.1` in the output, ask the system administrator to move the computer's network IP address to the beginning of the `/etc/hosts` file.

- If you have problems with OutOfMemory errors and the JVM crashing with JDK 1.3, try setting: `-XX:MaxPermSize=128m`. For WebLogic Integration, use the following setting: `-XX:MaxPermSize=256m`.
- For information about suggested values for some Solaris TCP and VM-related tunable parameters, see “[Operating System Tuning](#)” in *BEA WebLogic Server 7.0 Performance and Tuning*.

For more information about known issues with any components of this release, see the appropriate *Release Notes* document. For a complete list of *Release Notes* supporting WebLogic Platform 7.0, see:

<http://e-docs.bea.com/platform/docs70/interm/relnotes.html>

Sun Solaris 8 on SPARC with WebLogic Platform 7.0

Product Components Supported on this Configuration

	WebLogic Server	WebLogic Workshop	WebLogic Integration	WebLogic Portal
Run-time	✓	✓	✓	✓
Design/Dev Tools*	✓	✗	✗	✗

* For design and development tools support, see the “Configuration Requirements” section below.

✓ Supported
✗ Not supported

Note: The version of WebLogic Server included with WebLogic Platform 7.0 GA is version 7.0.0.1. It contains updates to the WebLogic Server 7.0 GA version (7.0.0.0). Support information that applies only to WebLogic Server 7.0 GA is identified below.

This section provides the following information:

- [Configuration Requirements](#)
- [Known Issues](#)

Related Information

- For information about supported database configurations, Web servers, and browsers, plus support for interoperability tools and WebLogic Platform product support information, see [WebLogic Platform 7.0 Supported Configurations](#).
- For details about Sun Solaris 8, visit Sun’s Solaris Web page at: <http://www.sun.com/solaris>.

- For Sun’s support services information site, see <http://www.sun.com/service/support>. If you have a support contract for the use of Solaris platforms, you may be able to obtain support for general Java issues (for example, JVM problems).
- You can run WebLogic software on Solaris using the SDK available from Sun Microsystems at: <http://java.sun.com/products/?frontpage-main>. BEA recommends using the latest available versions of the JVMs supported by BEA, except where noted otherwise in our *Supported Configurations* document.

Configuration Requirements

Table 8-1 Requirements for WebLogic Platform 7.0 on Sun Solaris 8 on SPARC

Operating System Version and Patches	Solaris 8	The Solaris operating system must have the latest Sun Java 2 SDK 1.3.1_03 patches applied. For additional information, see: http://java.sun.com/j2se/1.3/install-solaris-patches.html
Chip Architecture and Minimum Processor Speed	UltraSPARC (168 MHz)	
SDK	Sun Java 2 SDK 1.3.1_03 (32 bit)	<ul style="list-style-type: none">• Bundled with BEA WebLogic Platform and installed, automatically, under the BEA Home directory.• Supports the Java HotSpot™ Client and Server VMs• WebLogic Portal is configured to use the Sun Java 2 SDK 1.3.1 with the Java HotSpot Server VM. For additional information, see “Using the HotSpot Virtual Machine” in “Performance Tuning” in “System Administration” in the <i>WebLogic Portal Administration Guide</i>, which is available at the following URL: http://e-docs.bea.com/wlp/docs70/admin/sysadmin.htm
	Sun Java 2 SDK 1.3.1_02 (32 bit) and all later service packs of 1.3.1	Supported on WebLogic Server 7.0 GA only.

Table 8-1 Requirements for WebLogic Platform 7.0 on Sun Solaris 8 on SPARC (Continued)

Design and Development Tools	Supports WebLogic Server development tools. For more information about WebLogic Platform design and development tools support, see “Supported Configurations for Design and Development Tools in Version 7.0 GA” in <i>Supported Configurations for WebLogic Platform 7.0</i> .	
RAM	512 MB required; 1 GB recommended	
Disk Space	For any components of WebLogic Platform or for the full WebLogic Platform product, see Disk Space Requirements .	
Performance Pack	Included	
Node Manager	Java	
BEA jDrivers for Oracle	For this Oracle client version:	The following shared libraries are provided:
	Oracle 8.1.7	<ul style="list-style-type: none"> lib/solaris/oci817_8/libweblogicoci38.so lib/solaris/oci817_8/libweblogicoxa38.so
	Oracle 9.0.1	<ul style="list-style-type: none"> lib/solaris/oci901_8/libweblogicoci38.so lib/solaris/oci901_8/libweblogicoxa38.so

Known Issues

- The JIT (Just-In-Time) Compiler is supported only for 1.2.2_05a when the `export _JVM_ARGS="inline_instrs_jit=0"` directive is being used. This is due to two Sun bugs: #4333396 (JVM crash during JIT) and #4333696. The error message reads:


```
SIGABRT and JIT coredump: panic: Unexpected operand kind(10) in j86OpndImage.
```

These bugs also affect 1.2.1_04, so you must Disable aggressive inlining by the JIT with:
`export _JIT_ARGS=novinline.`
- 7.3.4 jDriver for Oracle is not supported with JDK 1.3.1.
- Some Solaris JVMs report an incorrect IP number. The IP number reported for the machine is the first number in the `/etc/hosts` file. Unfortunately, this number is frequently `127.0.0.1`, the standard loopback network address for the machine. This problem affects licenses granted for specific IP numbers. We have also observed this

problem in a cluster where an HTTP request is passed by a Web server or another WebLogic Server via the `HttpClusterServlet`, to a WebLogic Server running on a Solaris machine with this configuration problem. The `127.0.0.1` IP number is carried with the server's response. Subsequent calls to that machine time out because the IP number is incorrect.

To determine whether you have this problem on your Solaris computer, run the following command:

```
java utils.netAddresses
```

If you see `127.0.0.1` in the output, ask the system administrator to move the computer's network IP address to the beginning of the `/etc/hosts` file.

- If you have problems with `OutOfMemory` errors and the JVM crashing with JDK 1.3, try setting: `-XX:MaxPermSize=128m`. For WebLogic Integration, use the following setting: `-XX:MaxPermSize=256m`.
- For information about suggested values for some Solaris TCP and VM-related tunable parameters, see “[Operating System Tuning](#)” in *BEA WebLogic Server 7.0 Performance and Tuning*.

For more information about known issues with any components of this release, see the appropriate *Release Notes* document. For a complete list of *Release Notes* supporting WebLogic Platform 7.0, see:

<http://e-docs.bea.com/platform/docs70/interm/relnotes.html>