

Oracle® Grid Infrastructure

Grid Infrastructure Installation and Upgrade Guide



23ai for Linux
F46764-05
March 2025

The Oracle logo, consisting of a solid red square with the word "ORACLE" in white, uppercase, sans-serif font centered within it.

ORACLE®

Oracle Grid Infrastructure Grid Infrastructure Installation and Upgrade Guide, 23ai for Linux

F46764-05

Copyright © 2013, 2025, Oracle and/or its affiliates.

Primary Author: Subhash Chandra

Contributing Authors: Aparna Kamath, Douglas Williams, Mark Bauer, Prakash Jashnani, Janet Stern

Contributors: Markus Michalewicz, Aneesh Khandelwal, James Williams, Ian Cookson, Rajesh Dasari, Pallavi Kamath, Donald Graves, Jonathan Creighton, Angad Gokakkar, Srinivas Poovala, Prasad Bagal, Balaji Pagadala, Neha Avasthy, Mark Scardina, Hanlin Chien, Anil Nair, Apparsamy Perumal, Samarjeet Tomar, Akshay Shah, Kevin Jernigan, Eric Belden, Mark Fuller, Barbara Glover, Saar Maoz, Binoy Sukumaran

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software, software documentation, data (as defined in the Federal Acquisition Regulation), or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs (including any operating system, integrated software, any programs embedded, installed, or activated on delivered hardware, and modifications of such programs) and Oracle computer documentation or other Oracle data delivered to or accessed by U.S. Government end users are "commercial computer software," "commercial computer software documentation," or "limited rights data" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, reproduction, duplication, release, display, disclosure, modification, preparation of derivative works, and/or adaptation of i) Oracle programs (including any operating system, integrated software, any programs embedded, installed, or activated on delivered hardware, and modifications of such programs), ii) Oracle computer documentation and/or iii) other Oracle data, is subject to the rights and limitations specified in the license contained in the applicable contract. The terms governing the U.S. Government's use of Oracle cloud services are defined by the applicable contract for such services. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle®, Java, MySQL, and NetSuite are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Inside are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Epyc, and the AMD logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Contents

Preface

Audience	xiii
Documentation Accessibility	xiii
Diversity and Inclusion	xiv
Set Up Java Access Bridge to Implement Java Accessibility	xiv
Command Syntax	xiv
Conventions	xv

1 Oracle Grid Infrastructure Installation Checklist

Server Hardware Checklist for Oracle Grid Infrastructure	1-1
Operating System Checklist for Oracle Grid Infrastructure and Oracle RAC	1-2
Server Configuration Checklist for Oracle Grid Infrastructure	1-3
Network Checklist for Oracle Grid Infrastructure	1-5
User Environment Configuration Checklist for Oracle Grid Infrastructure	1-7
Storage Checklist for Oracle Grid Infrastructure	1-9
Cluster Deployment Checklist for Oracle Grid Infrastructure	1-9
Installer Planning Checklist for Oracle Grid Infrastructure	1-10

2 Checking and Configuring Server Hardware for Oracle Grid Infrastructure

Logging In to a Remote System Using X Window System	2-1
Checking Server Hardware and Memory Configuration	2-2

3 Automatically Configuring Oracle Linux with Oracle Database Preinstallation RPM

About the Oracle Database Preinstallation RPM	3-1
Overview of Oracle Linux Configuration with Oracle Database Preinstallation RPM	3-2
Installing the Oracle Database Preinstallation RPM Using ULN	3-3
Installing Oracle Database Preinstallation RPM During an Oracle Linux Installation	3-4
Installing Oracle Oracle Database Preinstallation RPM Using the Oracle Linux yum Server	3-5
Configure Additional Operating System Features	3-6

4 Configuring Operating Systems for Oracle Grid Infrastructure on Linux

Guidelines for Linux Operating System Installation	4-2
Completing a Minimal or Default Linux Installation	4-2
About Oracle Linux with the Unbreakable Enterprise Kernel	4-3
Configuring HugePages on Linux	4-4
Restrictions for HugePages and Transparent HugePages Configurations	4-6
Reviewing Operating System and Software Upgrade Best Practices	4-6
General Upgrade Best Practices	4-7
New Server Operating System Upgrade Option	4-7
Upgrading Operating System for an Oracle Grid Infrastructure Server	4-8
Oracle ASM Upgrade Notifications	4-9
Reviewing Operating System Security Common Practices	4-10
About Installation Fixup Scripts	4-10
About Automatic Self Correction	4-11
About Operating System Requirements	4-11
Operating System Requirements for x86-64 Linux Platforms	4-11
General Guidelines for Operating System Packages	4-12
Supported Oracle Linux 9 Distributions for x86-64	4-12
Supported Oracle Linux 8 Distributions for x86-64	4-15
Supported Red Hat Enterprise Linux 9 Distributions for x86-64	4-17
Supported Red Hat Enterprise Linux 8 Distributions for x86-64	4-18
Supported SUSE Linux Enterprise Server 15 Distributions for x86-64	4-19
Installing Operating System Packages	4-20
Additional Drivers and Software Packages for Linux	4-20
Installing PAM for Login Authentication on Linux	4-21
Installing OCFS2	4-21
Installation Requirements for ODBC and LDAP	4-22
About ODBC Drivers and Oracle Database	4-22
Installing ODBC Drivers for Linux x86-64	4-22
About LDAP and Oracle Plug-ins	4-22
Installing the LDAP Package	4-22
Installing Oracle Messaging Gateway	4-23
Installation Requirements for Programming Environments for Linux	4-23
Installation Requirements for Programming Environments for Linux x86-64	4-23
Installation Requirements for Web Browsers	4-24
Checking Kernel and Package Requirements for Linux	4-24
Setting Clock Source for VMs on Linux x86-64	4-25
Installing the cvuqdisk RPM for Linux	4-26
Reviewing HugePages Memory Allocation	4-26
Setting Transparent HugePages to madvise	4-26
Enabling the Name Service Cache Daemon	4-28

Verifying the Disk I/O Scheduler on Linux 8 and Later Systems	4-28
Using Automatic SSH Configuration During Installation	4-29
Setting Network Time Protocol for Cluster Time Synchronization	4-30
Verifying Digital Signature and Integrity of Installation Archive Files	4-31

5 Configuring Networks for Oracle Grid Infrastructure and Oracle RAC

About Oracle Grid Infrastructure Network Configuration Options	5-2
Understanding Network Addresses	5-3
About the Public IP Address	5-3
About the Private IP Address	5-3
About the Virtual IP Address	5-4
About the Grid Naming Service (GNS) Virtual IP Address	5-4
About the SCAN	5-5
About Shared SCAN	5-6
Network Interface Hardware Minimum Requirements	5-6
Private IP Interface Configuration Requirements	5-8
IPv4 and IPv6 Protocol Requirements	5-9
Oracle Grid Infrastructure IP Name and Address Requirements	5-10
About Oracle Grid Infrastructure Name Resolution Options	5-10
Cluster Name and SCAN Requirements	5-11
IP Name and Address Requirements For Grid Naming Service (GNS)	5-12
IP Name and Address Requirements for Manual Configuration of Cluster	5-12
Confirming the DNS Configuration for SCAN	5-13
Broadcast Requirements for Networks Used by Oracle Grid Infrastructure	5-14
Multicast Requirements for Networks Used by Oracle Grid Infrastructure	5-14
Domain Delegation to Grid Naming Service	5-15
Choosing a Subdomain Name for Use with Grid Naming Service	5-15
Configuration Requirements for Oracle Flex Clusters	5-15
Understanding Oracle Flex Clusters	5-16
About Oracle Flex ASM Clusters Networks	5-16
General Requirements for Oracle Flex Cluster Configuration	5-17
Oracle Flex Cluster DHCP-Assigned Virtual IP (VIP) Addresses	5-17
Oracle Flex Cluster Manually-Assigned Addresses	5-18
Grid Naming Service Cluster Configuration Example	5-18
Manual IP Address Configuration Example	5-19
Network Interface Configuration Options	5-21
Multiple Private Interconnects and Oracle Linux	5-21
Creating SCAN Client Data File	5-22

6 Configuring Users, Groups and Environments for Oracle Grid Infrastructure and Oracle Database

Creating Groups, Users and Paths for Oracle Grid Infrastructure	6-1
Determining If an Oracle Inventory and Oracle Inventory Group Exist	6-2
Creating the Oracle Inventory Group If an Oracle Inventory Does Not Exist	6-3
About Oracle Installation Owner Accounts	6-3
Restrictions for Oracle Software Installation Owners	6-4
Identifying an Oracle Software Owner User Account	6-5
About the Oracle Base Directory for the grid User	6-5
About the Oracle Home Directory for Oracle Grid Infrastructure Software	6-6
About Creating the Oracle Home and Oracle Base Directory	6-7
Oracle Installations with Standard and Job Role Separation Groups and Users	6-8
About Oracle Installations with Job Role Separation	6-8
Standard Oracle Database Groups for Database Administrators	6-9
Extended Oracle Database Groups for Job Role Separation	6-9
Creating an ASMSNMP User	6-10
Oracle Automatic Storage Management Groups for Job Role Separation	6-10
Creating Operating System Privileges Groups	6-11
Creating the OSASM Group	6-12
Creating the OSDBA for ASM Group	6-12
Creating the OSOPER for ASM Group	6-12
Creating the OSDBA Group for Database Installations	6-13
Creating an OSOPER Group for Database Installations	6-13
Creating the OSBACKUPDBA Group for Database Installations	6-13
Creating the OSDGDBA Group for Database Installations	6-14
Creating the OSKMDBA Group for Database Installations	6-14
Creating the OSRACDBA Group for Database Installations	6-14
Creating Operating System Oracle Installation User Accounts	6-14
Creating an Oracle Software Owner User	6-15
Modifying Oracle Owner User Groups	6-16
Identifying Existing User and Group IDs	6-16
Creating Identical Database Users and Groups on Other Cluster Nodes	6-16
Example of Creating Minimal Groups, Users, and Paths	6-18
Example of Creating Role-allocated Groups, Users, and Paths	6-19
Configuring Grid Infrastructure Software Owner User Environments	6-22
Environment Requirements for Oracle Software Owners	6-23
Procedure for Configuring Oracle Software Owner Environments	6-23
Checking Resource Limits for Oracle Software Installation Users	6-26
Setting Remote Display and X11 Forwarding Configuration	6-27
Preventing Installation Errors Caused by Terminal Output Commands	6-28
Enabling Intelligent Platform Management Interface (IPMI)	6-28

Requirements for Enabling IPMI	6-29
Configuring the IPMI Management Network	6-30
Configuring the Open IPMI Driver	6-30
Configuring the BMC	6-32
Configuring BMC Using IPMItool	6-32

7 Supported Storage Options for Oracle Database and Oracle Grid Infrastructure

Supported Storage Options for Oracle Grid Infrastructure	7-1
Oracle ACFS and Oracle ADVM	7-3
Oracle ACFS and Oracle ADVM Support on Linux x86–64	7-3
Restrictions and Guidelines for Oracle ACFS	7-4
Storage Considerations for Oracle Grid Infrastructure and Oracle RAC	7-5
Guidelines for Using Oracle ASM Disk Groups for Storage	7-6
Guidelines for Configuring Oracle ASM Disk Groups on NFS	7-6
Using Logical Volume Managers with Oracle Grid Infrastructure and Oracle RAC	7-8
Using a Cluster File System for Oracle Clusterware Files	7-8
About NFS Storage for Data Files	7-8
About Direct NFS Client Mounts to NFS Storage Devices	7-9

8 Configuring Storage for Oracle Grid Infrastructure

Configuring Storage for Oracle Automatic Storage Management	8-2
Identifying Storage Requirements for Oracle Automatic Storage Management	8-2
Oracle Clusterware Storage Space Requirements	8-7
Using an Existing Oracle ASM Disk Group	8-7
About Upgrading Existing Oracle Automatic Storage Management Instances	8-8
Selecting Disks to use with Oracle ASM Disk Groups	8-8
Specifying the Oracle ASM Disk Discovery String	8-9
Creating Files on a NAS Device for Use with Oracle Automatic Storage Management	8-9
Configuring Storage Device Path Persistence Using Oracle ASMFD	8-11
About Oracle ASM with Oracle ASM Filter Driver	8-11
Configuring Oracle ASM Filter Driver	8-12
Configuring Oracle ASM Filter Driver During Installation	8-12
Configuring Oracle ASM Filter Driver After Installation	8-13
About Migrating From Oracle ASMLib to Oracle ASM Filter Driver	8-15
Migrating Oracle ASM Disk Groups Including OCR or Voting Files	8-15
Migrating Oracle ASM Disk Groups with Oracle Cluster Registry or Voting Files	8-16
Determining If Oracle ASM Filter Driver Is Configured	8-17
Configuring NVMe Over Fabrics Storage Devices with Oracle ASM	8-17
About Using NVMe Over Fabrics Devices for Data Files	8-17

Requirements and Guidelines for NVMe Over Fabrics Storage	8-18
Creating an NVMe-oF Storage Target	8-18
Creating an NVMe Configuration File and Using NVMe-oF Devices	8-21
Using Disk Groups with Oracle Database Files on Oracle ASM	8-23
Identifying and Using Existing Oracle Database Disk Groups on Oracle ASM	8-23
Guidelines for Creating Disk Groups for Oracle Database Data Files	8-23
Creating Directories for Oracle Database Files	8-24
Configuring File System Storage for Oracle Database	8-25
Configuring NFS Buffer Size Parameters for Oracle Database	8-25
Checking TCP Network Protocol Buffer for Direct NFS Client	8-26
Creating an oranfstab File for Direct NFS Client	8-26
Enabling and Disabling Direct NFS Client Control of NFS	8-29
Enabling Hybrid Columnar Compression on Direct NFS Client	8-29
Creating Oracle ASM Client Data File	8-30
Configuring Oracle Advanced Cluster File System	8-30
Checking OCFS2 Version Manually	8-31

9 Installing Oracle Grid Infrastructure

About Image-Based Oracle Grid Infrastructure Installation	9-2
Setup Wizard Installation Options for Creating Images	9-2
Downloading the Software from Oracle Software Delivery Cloud Portal	9-3
Understanding Cluster Configuration Options	9-4
About Oracle Grid Infrastructure to Manage Oracle RAC Databases	9-4
About Oracle Grid Infrastructure to Manage Generic Applications	9-5
About Oracle Extended Clusters	9-5
Installing Oracle Grid Infrastructure for a New Cluster	9-6
About Oracle Grid Infrastructure Installation	9-6
Installing Oracle Grid Infrastructure to Manage Oracle RAC Databases	9-7
Installing Oracle Grid Infrastructure to Manage Generic Applications	9-13
Installing Oracle Grid Infrastructure Using Command-Line Interface	9-19
Installing Oracle Grid Infrastructure Using a Cluster Configuration File	9-21
Installing Only the Oracle Grid Infrastructure Software	9-22
Installing Software Binaries for Oracle Grid Infrastructure for a Cluster	9-23
Configuring Software Binaries for Oracle Grid Infrastructure for a Cluster	9-24
Configuring the Software Binaries Using a Response File	9-24
Setting Ping Targets for Network Checks	9-25
About Deploying Oracle Grid Infrastructure Using Oracle Fleet Patching and Provisioning	9-25
Confirming Oracle Clusterware Function	9-27
Confirming Oracle ASM Function for Oracle Clusterware Files	9-27
Understanding Offline Processes in Oracle Grid Infrastructure	9-28

10 Patching Oracle Grid Infrastructure

About Individual Oracle Grid Infrastructure Patches	10-1
About Oracle Grid Infrastructure Software Patch Levels	10-2
About Zero-Downtime Oracle Grid Infrastructure Patching	10-2
Applying Patches to Oracle Grid Infrastructure	10-3
Applying Patches Using Zero-Downtime Oracle Grid Infrastructure Patching	10-3
Applying Patches During an Oracle Grid Infrastructure Installation or Upgrade	10-5
Applying Patches After an Oracle Grid Infrastructure Installation or Upgrade	10-6
Applying Patches when Oracle Clusterware Fails to Start	10-6
Patching and Switching Oracle Grid Infrastructure Homes	10-8
Patching Oracle Grid Infrastructure Using Oracle FPP Local Mode	10-9
Changing the Oracle Grid Infrastructure Base Path	10-10

11 Upgrading Oracle Grid Infrastructure

Understanding Out-of-Place Upgrade	11-2
About Oracle Grid Infrastructure Upgrade and Downgrade	11-2
Options for Oracle Grid Infrastructure Upgrades	11-3
Restrictions for Oracle Grid Infrastructure Upgrades	11-3
Preparing to Upgrade an Existing Oracle Clusterware Installation	11-5
Upgrade Checklist for Oracle Grid Infrastructure	11-5
Checks to Complete Before Upgrading Oracle Grid Infrastructure	11-7
Removing Grid Infrastructure Management Repository	11-8
Moving Oracle Clusterware Files from NFS to Oracle ASM	11-9
Running the Oracle ORAchk Upgrade Readiness Assessment	11-10
Using CVU to Validate Readiness for Oracle Clusterware Upgrades	11-10
About the CVU Upgrade Validation Command Options	11-11
Standalone CVU Home	11-12
Example of Verifying System Upgrade Readiness for Grid Infrastructure	11-13
Using Dry-Run Upgrade Mode to Check System Upgrade Readiness	11-13
About Oracle Grid Infrastructure Dry-Run Upgrade Mode	11-13
Performing Dry-Run Upgrade Using Oracle Universal Installer	11-14
Understanding Rolling Upgrades Using Batches	11-16
Performing Rolling Upgrade of Oracle Grid Infrastructure	11-16
Upgrading Oracle Grid Infrastructure Using Setup Wizard	11-17
Upgrading Oracle Grid Infrastructure Using Command-Line Interface	11-20
Completing an Oracle Clusterware Upgrade when Nodes Become Unreachable	11-22
Joining Inaccessible Nodes After Forcing an Upgrade	11-23
Changing the First Node for Install and Upgrade	11-23
About Upgrading Oracle Grid Infrastructure Using Oracle Fleet Patching and Provisioning	11-24
Updating Oracle Enterprise Manager Cloud Control Target Parameters	11-24

Updating the Enterprise Manager Cloud Control Target After Upgrades	11-25
Updating the Enterprise Manager Agent Base Script After Upgrades	11-25
Registering Resources with Oracle Enterprise Manager After Upgrades	11-26
Unlocking and Deinstalling the Previous Release Grid Home	11-26
Checking Cluster Health Monitor Repository Size After Upgrading	11-27
Downgrading Oracle Clusterware to an Earlier Release	11-28
About Oracle Grid Infrastructure Downgrades	11-28
Options for Oracle Grid Infrastructure Downgrades	11-29
Restrictions for Oracle Grid Infrastructure Downgrades	11-29
Downgrading Oracle Grid Infrastructure	11-29
Downgrading Oracle Grid Infrastructure when Upgrade Fails	11-30
Downgrading Oracle Grid Infrastructure Using Online Terminate Upgrade	11-31
Completing Failed or Interrupted Installations and Upgrades	11-32
Completing Failed Installations and Upgrades	11-32
Continuing Incomplete Upgrade of First Node	11-33
Continuing Incomplete Upgrades on Remote Nodes	11-33
Continuing Incomplete Installation on First Node	11-34
Continuing Incomplete Installation on Remote Nodes	11-34

12 Oracle Grid Infrastructure Postinstallation Tasks

Required Postinstallation Tasks	12-1
Downloading Release Update Patches	12-2
Recommended Postinstallation Tasks	12-3
About Installing Oracle Autonomous Health Framework	12-3
Creating a Fast Recovery Area	12-4
About the Fast Recovery Area and the Fast Recovery Area Disk Group	12-4
Creating the Fast Recovery Area Disk Group	12-5
Checking the SCAN Configuration	12-5
Setting Resource Limits for Oracle Clusterware and Associated Databases and Applications	12-6
About Changes in Default SGA Permissions for Oracle Database	12-6
Using Earlier Oracle Database Releases with Oracle Grid Infrastructure	12-7
General Restrictions for Using Earlier Oracle Database Releases	12-7
Using ASMCA to Administer Disk Groups for Earlier Database Releases	12-8
Using the Correct LSNRCTL Commands	12-8
Relinking Oracle Grid Infrastructure for a Cluster Binaries	12-8

13 Removing Oracle Database Software

About Oracle Deinstallation Options	13-1
Oracle Deinstallation (Deinstall)	13-3

Unlocking and Deinstalling the Previous Release Grid Home	13-5
Deinstallation Examples for Oracle Database	13-6
Deinstallation Response File Example for Oracle Grid Infrastructure for a Cluster	13-7
Migrating Standalone Oracle Grid Infrastructure Servers to a Cluster	13-9
Changing the Oracle Grid Infrastructure Home Path	13-12

A Oracle Grid Infrastructure Command-Line Options

gridSetup.sh Command	A-1
gridSetup.sh -setupHome	A-3
gridSetup.sh -setupHomeAs	A-4
gridSetup.sh -configureCluster	A-5
gridSetup.sh -switchGridhome	A-9
gridSetup.sh -upgrade	A-10
gridSetup.sh -downgrade	A-11
gridSetup.sh -createGoldImage	A-12
gridSetup.sh -addNode	A-12
gridSetup.sh -deleteNode	A-13

B Response Files

Reasons for Using Silent Mode or Response File Mode	B-1
Using Response Files	B-2
Preparing Response Files	B-2
Editing a Response File Template	B-2
Recording Response Files	B-4
Running Oracle Universal Installer Using a Response File	B-5
Postinstallation Configuration Using Response File Created During Installation	B-6
Using the Installation Response File for Postinstallation Configuration	B-6
Running Postinstallation Configuration Using Response File	B-8

C Completing Preinstallation Tasks Manually

Configuring SSH Manually on All Cluster Nodes	C-1
About Passwordless SSH Configuration	C-1
Checking Existing SSH Configuration on the System	C-2
Configuring SSH on Cluster Nodes	C-2
Create SSH Directory and Create SSH Keys On Each Node	C-2
Add All Keys to a Common authorized_keys File	C-3
Enabling SSH User Equivalency on Cluster Nodes	C-5
Configuring Storage Device Path Persistence Using Oracle ASMLIB	C-5
About Oracle ASM with Oracle ASMLIB	C-6

Installing and Configuring Oracle ASMLIB Software	C-7
Configuring Disk Devices to Use Oracle ASMLIB	C-10
Administering Oracle ASMLIB and Disks	C-12
Configuring Oracle ASMLIB for Multipath Disks	C-13
About Using Oracle ASM with Multipath Disks	C-13
About Disk Scan Ordering	C-14
Configuring Disk Scan Ordering to Select Multipath Disks	C-14
Configuring Disk Order Scan to Exclude Single Path Disks	C-15
Deinstalling Oracle ASMLIB On Oracle Grid Infrastructure	C-16
Configuring Storage Device Path Persistence Manually	C-16
About Device Path Persistence	C-17
Configuring Device Persistence Manually for Oracle ASM	C-17
Configuring Kernel Parameters for Linux	C-19
Minimum Parameter Settings for Installation	C-20
Changing Kernel Parameter Values	C-21
Configuring Additional Kernel Settings for SUSE Linux	C-23
Setting UDP and TCP Kernel Parameters Manually	C-23
Configuring Default Thread Limits Value for SUSE Linux	C-24

D Optimal Flexible Architecture

About the Optimal Flexible Architecture Standard	D-1
About Multiple Oracle Homes Support	D-2
About the Oracle Inventory Directory and Installation	D-2
Oracle Base Directory Naming Convention	D-4
Oracle Home Directory Naming Convention	D-4
Optimal Flexible Architecture File Path Examples	D-5

Preface

This guide explains how to configure a server in preparation for installing and configuring an Oracle Grid Infrastructure installation (Oracle Clusterware and Oracle Automatic Storage Management).

It also explains how to configure a server and storage in preparation for an Oracle Real Application Clusters (Oracle RAC) installation.

- [Audience](#)
- [Documentation Accessibility](#)
- [Diversity and Inclusion](#)
- [Set Up Java Access Bridge to Implement Java Accessibility](#)
Install Java Access Bridge so that assistive technologies on Microsoft Windows systems can use the Java Accessibility API.
- [Command Syntax](#)
Refer to these command syntax conventions to understand command examples in this guide.
- [Conventions](#)

Audience

This guide provides configuration information for network and system administrators, and database installation information for database administrators (DBAs) who install and configure Oracle Clusterware and Oracle Automatic Storage Management in an Oracle Grid Infrastructure for a cluster installation.

For users with specialized system roles who intend to install Oracle RAC, this book is intended to be used by system administrators, network administrators, or storage administrators to configure a system in preparation for an Oracle Grid Infrastructure for a cluster installation, and complete all configuration tasks that require operating system root privileges. When Oracle Grid Infrastructure installation and configuration is completed successfully, a system administrator should only need to provide configuration information and to grant access to the database administrator to run scripts as root during an Oracle RAC installation.

This guide assumes that you are familiar with Oracle Database concepts.

Documentation Accessibility

For information about Oracle's commitment to accessibility, visit the Oracle Accessibility Program website at <http://www.oracle.com/pls/topic/lookup?ctx=acc&id=docacc>.

Access to Oracle Support

Oracle customer access to and use of Oracle support services will be pursuant to the terms and conditions specified in their Oracle order for the applicable services.

Diversity and Inclusion

Oracle is fully committed to diversity and inclusion. Oracle respects and values having a diverse workforce that increases thought leadership and innovation. As part of our initiative to build a more inclusive culture that positively impacts our employees, customers, and partners, we are working to remove insensitive terms from our products and documentation. We are also mindful of the necessity to maintain compatibility with our customers' existing technologies and the need to ensure continuity of service as Oracle's offerings and industry standards evolve. Because of these technical constraints, our effort to remove insensitive terms is ongoing and will take time and external cooperation.

Set Up Java Access Bridge to Implement Java Accessibility

Install Java Access Bridge so that assistive technologies on Microsoft Windows systems can use the Java Accessibility API.

Java Access Bridge is a technology that enables Java applications and applets that implement the Java Accessibility API to be visible to assistive technologies on Microsoft Windows systems.

Refer to *Java Platform, Standard Edition Accessibility Guide* for information about the minimum supported versions of assistive technologies required to use Java Access Bridge. Also refer to this guide to obtain installation and testing instructions, and instructions for how to use Java Access Bridge.

Related Topics

- *Java Platform, Standard Edition Java Accessibility Guide*

Command Syntax

Refer to these command syntax conventions to understand command examples in this guide.

Convention	Description
\$	Bourne or BASH shell prompt in a command example. Do not enter the prompt as part of the command.
%	C Shell prompt in a command example. Do not enter the prompt as part of the command.
#	Superuser (root) prompt in a command example. Do not enter the prompt as part of the command.
monospace	UNIX command syntax
backslash \	A backslash is the UNIX and Linux command continuation character. It is used in command examples that are too long to fit on a single line. Enter the command as displayed (with a backslash) or enter it on a single line without a backslash: <pre>dd if=/dev/rdskc0t1d0s6 of=/dev/rst0 bs=10b \ count=10000</pre>
braces { }	Braces indicate required items: <pre>.DEFINE {macro1}</pre>

Convention	Description
brackets []	Brackets indicate optional items: <code>cvtcrt termname [outfile]</code>
ellipses ...	Ellipses indicate an arbitrary number of similar items: <code>CHKVAL fieldname value1 value2 ... valueN</code>
<i>italic</i>	Italic type indicates a variable. Substitute a value for the variable: <code><i>library_name</i></code>
vertical line	A vertical line indicates a choice within braces or brackets: <code>FILE filesize [K M]</code>

Conventions

The following text conventions are used in this document:

Convention	Meaning
boldface	Boldface type indicates graphical user interface elements associated with an action, or terms defined in text or the glossary.
<i>italic</i>	Italic type indicates book titles, emphasis, or placeholder variables for which you supply particular values.
monospace	Monospace type indicates commands within a paragraph, URLs, code in examples, text that appears on the screen, or text that you enter.

1

Oracle Grid Infrastructure Installation Checklist

Use checklists to plan and carry out Oracle Grid Infrastructure (Oracle Clusterware and Oracle Automatic Storage Management) installation.

Oracle recommends that you use checklists as part of your installation planning process. Using this checklist can help you to confirm that your server hardware and configuration meet minimum requirements for this release, and to ensure you carry out a successful installation.

- [Server Hardware Checklist for Oracle Grid Infrastructure](#)
Review server hardware requirements for Oracle Grid Infrastructure installation.
- [Operating System Checklist for Oracle Grid Infrastructure and Oracle RAC](#)
Review the checklist for operating system requirements for Oracle Grid Infrastructure installation.
- [Server Configuration Checklist for Oracle Grid Infrastructure](#)
Use this checklist to check minimum server configuration requirements for Oracle Grid Infrastructure installations.
- [Network Checklist for Oracle Grid Infrastructure](#)
Review this network checklist for Oracle Grid Infrastructure installation to ensure that you have required hardware, names, and addresses for the cluster.
- [User Environment Configuration Checklist for Oracle Grid Infrastructure](#)
Use this checklist to plan operating system users, groups, and environments for Oracle Grid Infrastructure installation.
- [Storage Checklist for Oracle Grid Infrastructure](#)
Review the checklist for storage hardware and configuration requirements for Oracle Grid Infrastructure installation.
- [Cluster Deployment Checklist for Oracle Grid Infrastructure](#)
Review the checklist for planning your cluster deployment Oracle Grid Infrastructure installation.
- [Installer Planning Checklist for Oracle Grid Infrastructure](#)
Review the checklist for planning your Oracle Grid Infrastructure installation before starting Oracle Universal Installer.



Server Hardware Checklist for Oracle Grid Infrastructure

Review server hardware requirements for Oracle Grid Infrastructure installation.

Table 1-1 Server Hardware Checklist for Oracle Grid Infrastructure

Check	Task
Runlevel	3 or 5

Table 1-1 (Cont.) Server Hardware Checklist for Oracle Grid Infrastructure

Check	Task
Server Display Cards	At least 1024 x 768 display resolution for Oracle Universal Installer.
<div style="border: 1px solid #0070C0; padding: 10px; margin: 10px 0;"> <p> Note:</p> <p>If you are planning on performing a silent installation, or want to use graphics connectivity like VNC or related protocols, no server graphics card is needed.</p> </div>	
Minimum Random Access Memory (RAM)	At least 8 GB RAM for Oracle Grid Infrastructure installations.
Intelligent Platform Management Interface (IPMI)	IPMI cards installed and configured, with IPMI administrator account information available to the person running the installation. Ensure baseboard management controller (BMC) interfaces are configured, and have an administration account username and password to provide when prompted during installation.
<div style="border: 1px solid #0070C0; padding: 10px; margin: 10px 0;"> <p> Note:</p> <p>You must configure the IPMI driver either on all or none of the cluster nodes.</p> </div>	

Operating System Checklist for Oracle Grid Infrastructure and Oracle RAC

Review the checklist for operating system requirements for Oracle Grid Infrastructure installation.

Table 1-2 Operating System General Checklist for Oracle Grid Infrastructure and Oracle RAC

Check	Task
Operating system general requirements	<p>OpenSSH installed manually, if you do not have it installed already as part of a default Linux installation.</p> <p>Review the system requirements section for a list of minimum package requirements. Use the same operating system kernel and packages on each cluster member node.</p> <ul style="list-style-type: none"> Oracle Linux 9.2 with the Unbreakable Enterprise Kernel 7: 5.15.0-201.135.6.el9uek.x86_64 or later Oracle Linux 9.2 with the Red Hat Compatible Kernel: 5.14.0-284.30.1.el9_2.x86_64 or later Oracle Linux 8.8 with the Unbreakable Enterprise Kernel 7: 5.15.0-202.135.2.el8uek.x86_64 or later Oracle Linux 8.6 with the Unbreakable Enterprise Kernel 6: 5.4.17-2136.312.3.4.el8uek.x86_64 or later Oracle Linux 8.6 with the Red Hat Compatible Kernel: 4.18.0-372.26.1.0.1.el8_6.x86_64 or later Red Hat Enterprise Linux 9.2: 5.14.0-284.30.1.el9_2.x86_64 or later Red Hat Enterprise Linux 8.6: 4.18.0-372.26.1.0.1.el8_6.x86_64 or later SUSE Linux Enterprise Server 15 SP5 (x86_64): 5.14.21-150500.53-default or later <p>Review the system requirements section for a list of minimum package requirements.</p>
Oracle Database Preinstallation RPM for Oracle Linux	If you use Oracle Linux, then Oracle recommends that you run an Oracle Database preinstallation RPM for your Linux release to configure your operating system for Oracle Database and Oracle Grid Infrastructure installations.
Virtualization Technologies	For information about supported virtualization technologies for Oracle Database, refer to the virtualization matrix: https://www.oracle.com/database/technologies/virtualization-matrix.html
Disable Transparent HugePages	Oracle recommends that you disable Transparent HugePages and use standard HugePages for enhanced performance.

Related Topics

- [Operating System Requirements for x86-64 Linux Platforms](#)
The Linux distributions and packages listed in this section are supported for this release on x86-64.

Server Configuration Checklist for Oracle Grid Infrastructure

Use this checklist to check minimum server configuration requirements for Oracle Grid Infrastructure installations.

Table 1-3 Server Configuration Checklist for Oracle Grid Infrastructure

Check	Task
Disk space allocated to the temporary file system	At least 1 GB of space in the temporary disk space (/tmp) directory.

Table 1-3 (Cont.) Server Configuration Checklist for Oracle Grid Infrastructure

Check	Task
Swap space allocation relative to RAM	Between 4 GB and 16 GB: Equal to RAM More than 16 GB: 16 GB Note: If you enable HugePages for your Linux servers, then you should deduct the memory allocated to HugePages from the available RAM before calculating swap space.
HugePages memory allocation	Allocate memory to HugePages large enough for the System Global Areas (SGA) of all databases planned to run on the cluster.
Mount point paths for the software binaries	Oracle recommends that you create an Optimal Flexible Architecture configuration as described in the appendix "Optimal Flexible Architecture" in <i>Oracle Grid Infrastructure Installation and Upgrade Guide</i> for your platform.
Ensure that the Oracle home (the Oracle home path you select for Oracle Database) uses only ASCII characters	The ASCII character restriction includes installation owner user names, which are used as a default for some home paths, as well as other directory names you may select for paths.
Set locale (if needed)	Specify the language and the territory, or locale, in which you want to use Oracle components. A locale is a linguistic and cultural environment in which a system or program is running. NLS (National Language Support) parameters determine the locale-specific behavior on both servers and clients. The locale setting of a component determines the language of the user interface of the component, and the globalization behavior, such as date and number formatting.
Set Network Time Protocol for Cluster Time Synchronization	Oracle Clusterware requires the same time zone environment variable setting on all cluster nodes. Ensure that you set the time zone synchronization across all cluster nodes using an operating system configured network time protocol (NTP).
<div style="border-left: 2px solid #0070C0; padding-left: 10px; margin-bottom: 10px;">  Note: Cluster Time Synchronization Service (CTSS) is desupported in Oracle Database 23ai. </div>	
Check Shared Memory File System Mount	By default, your operating system includes an entry in <code>/etc/fstab</code> to mount <code>/dev/shm</code> . However, if your Configuration Verification Utility (CVU) or Oracle Universal Installer (OUI) checks fail, then ensure that the <code>/dev/shm</code> mount area is of type <code>tmpfs</code> and is mounted with the following options: <ul style="list-style-type: none"> • <code>rw</code> and <code>exec</code> permissions set on it • Without <code>noexec</code> or <code>nosuid</code> set on it Note: Your operating system usually sets these options as the default permissions. If they are set by the operating system, then they are not listed on the mount options.
Symlinks	Oracle home or Oracle base cannot be <code>symlinks</code> , nor can any of their parent directories, all the way to up to the <code>root</code> directory.

Related Topics

- [Optimal Flexible Architecture](#)
Oracle Optimal Flexible Architecture (OFA) rules are a set of configuration guidelines created to ensure well-organized Oracle installations, which simplifies administration, support and maintenance.

Network Checklist for Oracle Grid Infrastructure

Review this network checklist for Oracle Grid Infrastructure installation to ensure that you have required hardware, names, and addresses for the cluster.

About Oracle Grid Infrastructure Network Configuration


During installation, you designate interfaces for use as public, private, or Oracle ASM interfaces. You can also designate interfaces that are in use for other purposes, such as a network file system, and not available for Oracle Grid Infrastructure use.

If you use a third-party cluster software, then the public host name information is obtained from that software.

Table 1-4 Network Configuration Tasks for Oracle Grid Infrastructure and Oracle RAC

Check	Task
Public network hardware	<ul style="list-style-type: none"> • Public network switch (redundant switches recommended) connected to a public gateway and to the public interface ports for each cluster member node. • Ethernet interface card (redundant network cards recommended, bonded as one Ethernet port name). • The switches and network interfaces must be at least 1 GbE. For NVMe over Fabrics (NVMe-oF) storage devices, Oracle recommends that you use a 25 GbE or higher Ethernet network interface card. • The network protocol is Transmission Control Protocol (TCP) and Internet Protocol (IP).
Private network hardware for the interconnect	<ul style="list-style-type: none"> • Private dedicated network switches (redundant switches recommended), connected to the private interface ports for each cluster member node. Note: If you have more than one private network interface card for each server, then Oracle Clusterware automatically associates these interfaces for the private network using Grid Interprocess Communication (GIPC) and Grid Infrastructure Redundant Interconnect, also known as Cluster High Availability IP (HAIP). • The switches and network interfaces must be at least 1 GbE. For NVMe over Fabrics (NVMe-oF) storage devices, Oracle recommends that you use a 25 GbE or higher Ethernet network interface card. • The interconnect must support the user datagram protocol (UDP). • Jumbo Frames (Ethernet frames greater than 1500 bits) are not an IEEE standard, but can reduce UDP overhead if properly configured. Oracle recommends the use of Jumbo Frames for interconnects. However, be aware that you must load-test your system, and ensure that they are enabled throughout the stack.
Oracle Flex ASM Network Hardware	Oracle Flex ASM can use either the same private networks as Oracle Clusterware, or use its own dedicated private networks. Each network can be classified PUBLIC or PRIVATE+ASM or PRIVATE or ASM. Oracle ASM networks use the TCP protocol.

Table 1-4 (Cont.) Network Configuration Tasks for Oracle Grid Infrastructure and Oracle RAC

Check	Task
Cluster Names and Addresses	<p>Determine and configure the following names and addresses for the cluster:</p> <ul style="list-style-type: none"> Cluster name: Decide a name for the cluster, and be prepared to enter it during installation. The cluster name should have the following characteristics: <ul style="list-style-type: none"> Globally unique across all hosts, even across different DNS domains. At least one character long and less than or equal to 15 characters long. Consist of the same character set used for host names, in accordance with RFC 1123: Hyphens (-), and single-byte alphanumeric characters (a to z, A to Z, and 0 to 9). If you use third-party vendor clusterware, then Oracle recommends that you use the vendor cluster name. Grid Naming Service Virtual IP Address (GNS VIP): If you plan to use GNS, then configure a GNS name and fixed address in DNS for the GNS VIP, and configure a subdomain on your DNS delegated to the GNS VIP for resolution of cluster addresses. GNS domain delegation is mandatory with dynamic public networks (DHCP, autoconfiguration).
<div style="border-left: 2px solid #0070C0; padding-left: 10px;"> <p> Note:</p> <p>The Highly Available Grid Naming Service feature of Grid Naming Service (GNS) in Oracle Grid Infrastructure is deprecated in Oracle Database 23ai.</p> </div>	
<ul style="list-style-type: none"> Single Client Access Name (SCAN) and addresses Using Grid Naming Service Resolution: Do not configure SCAN names and addresses in your DNS. SCAN names are managed by GNS. Using Manual Configuration and DNS resolution: Configure a SCAN name to resolve to three addresses on the domain name service (DNS). 	
Node Public, Private and Virtual IP names and Addresses	<p>If you are not using GNS, then configure the following for each node:</p> <ul style="list-style-type: none"> Public node name and address, configured in the DNS and in <code>/etc/hosts</code> (for example, <code>node1.example.com</code>, address <code>192.0.2.10</code>). The public node name should be the primary host name of each node, which is the name displayed by the <code>hostname</code> command. Private node address, configured on the private interface for each node. The private subnet that the private interfaces use must connect all the nodes you intend to have as cluster members. Oracle recommends that the network you select for the private network uses an address range defined as private by RFC 1918. Public node virtual IP name and address (for example, <code>node1-vip.example.com</code>, address <code>192.0.2.11</code>). If you are not using dynamic networks with GNS and subdomain delegation, then determine a virtual host name for each node. A virtual host name is a public node name that is used to reroute client requests sent to the node if the node is down. Oracle Database uses VIPs for client-to-database connections, so the VIP address must be publicly accessible. Oracle recommends that you provide a name in the format <code>hostname-vip</code>. For example: <code>myclstr2-vip</code>.

Related Topics

- [Understanding Oracle Flex Clusters](#)
Starting with Oracle Grid Infrastructure 12c Release 2 (12.2), Oracle Grid Infrastructure cluster configurations are Oracle Flex Clusters deployments.
- [About Oracle Flex ASM Clusters Networks](#)
Oracle ASM is configured as part of an Oracle Flex Cluster installation within Oracle Grid Infrastructure to provide storage services.
- [General Requirements for Oracle Flex Cluster Configuration](#)
Review this information about network requirements for Oracle Flex Cluster configuration.


User Environment Configuration Checklist for Oracle Grid Infrastructure

Use this checklist to plan operating system users, groups, and environments for Oracle Grid Infrastructure installation.

Table 1-5 User Environment Configuration for Oracle Grid Infrastructure

Check	Task
Review Oracle Inventory (oraInventory) and OINSTALL Group Requirements	<p>The Oracle Inventory directory is the central inventory of Oracle software installed on your system. It should be the primary group for all Oracle software installation owners. Users who have the Oracle Inventory group as their primary group are granted the OINSTALL privilege to read and write to the central inventory.</p> <ul style="list-style-type: none"> • If you have an existing installation, then OUI detects the existing oraInventory directory from the <code>/etc/oraInst.loc</code> file, and uses this location. • If you are installing Oracle software for the first time, then OUI creates an Oracle base and central inventory, and creates an Oracle inventory using information in the following priority: <ul style="list-style-type: none"> – In the path indicated in the ORACLE_BASE environment variable set for the installation owner user account. – In an Optimal Flexible Architecture (OFA) path (u[01–99]/app/owner where <i>owner</i> is the name of the user account running the installation), if that user account has permissions to write to that path. – In the user home directory, in the path <code>/app/owner</code>, where <i>owner</i> is the name of the user account running the installation. <p>Ensure that the group designated as the OINSTALL group is available as the primary group for all planned Oracle software installation owners.</p>

Table 1-5 (Cont.) User Environment Configuration for Oracle Grid Infrastructure

Check	Task
Create operating system groups and users for standard or role-allocated system privileges	<p>Create operating system groups and users depending on your security requirements, as described in this installation guide.</p> <p>Set resource limits settings and other requirements for Oracle software installation owners.</p> <p>Group and user names must use only ASCII characters.</p>
<div style="border-left: 2px solid #0070C0; padding-left: 10px;">  Note: Do not delete an existing daemon user. If a daemon user has been deleted, then you must add it back. </div>	
Unset Oracle Software Environment Variables	<p>If you have an existing Oracle software installation, and you are using the same user to install this installation, then unset the following environment variables: \$ORACLE_HOME; \$ORA_NLS10; \$TNS_ADMIN.</p> <p>If you have set \$ORA_CRS_HOME as an environment variable, then unset it before starting an installation or upgrade. Do not use \$ORA_CRS_HOME as a user environment variable, except as directed by Oracle Support.</p>
Configure the Oracle Software Owner Environment	<p>Configure the environment of the oracle or grid user by performing the following tasks:</p> <ul style="list-style-type: none"> • Set the default file mode creation mask (umask) to 022 in the shell startup file. • Set the DISPLAY environment variable.
Determine root privilege delegation option for installation	<p>During installation, you are asked to run configuration scripts as the root user. You can either run these scripts manually as root when prompted, or during installation you can provide configuration information and passwords using a root privilege delegation option.</p> <p>To run root scripts automatically, select Automatically run configuration scripts. during installation. To use the automatic configuration option, the root user credentials for all cluster member nodes must use the same password.</p> <ul style="list-style-type: none"> • Use root user credentials Provide the superuser password for cluster member node servers. • Use sudo sudo is a UNIX and Linux utility that allows members of the sudoers list privileges to run individual commands as root. Provide the user name and password of an operating system user who is a member of sudoers, and is authorized to run sudo on each cluster member node. To enable sudo, have a system administrator with the appropriate privileges configure a user who is a member of the sudoers list, and provide the user name and password when prompted during installation.

Storage Checklist for Oracle Grid Infrastructure

Review the checklist for storage hardware and configuration requirements for Oracle Grid Infrastructure installation.

Table 1-6 Oracle Grid Infrastructure Storage Configuration Checks

Check	Task
Minimum disk space (local or shared) for Oracle Grid Infrastructure Software	<ul style="list-style-type: none"> At least 12 GB of space for the Oracle Grid Infrastructure for a cluster home (Grid home). Oracle recommends that you allocate 100 GB to allow additional space for patches. At least 10 GB for Oracle Database Enterprise Edition. Allocate additional storage space as per your cluster configuration, as described in <i>Oracle Clusterware Storage Space Requirements</i>.
Select Oracle ASM Storage Options	<p>During installation, based on the cluster configuration, you are asked to provide Oracle ASM storage paths for the Oracle Clusterware files. These path locations must be writable by the Oracle Grid Infrastructure installation owner (Grid user). These locations must be shared across all nodes of the cluster on Oracle ASM because the files in the Oracle ASM disk group created during installation must be available to all cluster member nodes.</p> <ul style="list-style-type: none"> For Oracle Grid Infrastructure deployment to manage Oracle RAC databases, shared storage, either Oracle ASM or shared file system, is locally mounted on each of the cluster nodes. <p>Voting files are files that Oracle Clusterware uses to verify cluster node membership and status. Oracle Cluster Registry files (OCR) contain cluster and database configuration information for Oracle Clusterware.</p>

Related Topics

- [Oracle Clusterware Storage Space Requirements](#)
Use this information to determine the minimum number of disks and the minimum disk space requirements based on the redundancy type, for installing Oracle Clusterware files for various Oracle Cluster deployments.

Cluster Deployment Checklist for Oracle Grid Infrastructure

Review the checklist for planning your cluster deployment Oracle Grid Infrastructure installation.

Table 1-7 Oracle Grid Infrastructure Cluster Deployment Checklist

Check	Task
Configure an Oracle Cluster that hosts all Oracle Grid Infrastructure services and Oracle ASM locally and accesses storage directly	<p>Oracle Grid Infrastructure supports the following deployment options:</p> <ul style="list-style-type: none"> Configure cluster to manage Oracle RAC databases: Use this option to configure a cluster that can host Oracle RAC databases. Configure cluster to manage generic applications: Use this option to configure a cluster with minimum requirements to manage your applications. Configure as an Oracle Extended cluster: Use the Oracle Extended Cluster option to extend an Oracle RAC cluster across two, or more, separate sites, each equipped with its own storage.

Related Topics

- [Understanding Cluster Configuration Options](#)
 Review these topics to understand the cluster configuration options available in Oracle Grid Infrastructure.

Installer Planning Checklist for Oracle Grid Infrastructure

Review the checklist for planning your Oracle Grid Infrastructure installation before starting Oracle Universal Installer.

Table 1-8 Oracle Universal Installer Checklist for Oracle Grid Infrastructure Installation

Check	Task
Read the Release Notes	Review release notes for your platform, which are available for your release at the following URL: http://www.oracle.com/technetwork/indexes/documentation/index.html
Review the Licensing Information	You are permitted to use only those components in the Oracle Database media pack for which you have purchased licenses. For more information, see: <i>Oracle Database Licensing Information User Manual</i>
Run OUI with CVU and use fixup scripts	Oracle Universal Installer is fully integrated with Configuration Verification Utility (CVU), automating many CVU prerequisite checks. Oracle Universal Installer runs all prerequisite checks and creates fixup scripts when you run the installer. You can also run CVU commands manually to check system readiness. For more information, see: <i>Oracle Clusterware Administration and Deployment Guide</i>
Download and run Oracle ORAchk for runtime and upgrade checks, or runtime health checks	The Oracle ORAchk utility provides system checks that can help to prevent issues after installation. These checks include kernel requirements, operating system resource allocations, and other system requirements. Use the Oracle ORAchk Upgrade Readiness Assessment to obtain an automated upgrade-specific system health check for upgrades. For example: <pre>./orachk -u -o pre</pre> The Oracle ORAchk Upgrade Readiness Assessment automates many of the manual pre- and post-upgrade checks described in Oracle upgrade documentation.
Ensure cron jobs do not run during installation	If the installer is running when daily cron jobs start, then you may encounter unexplained installation problems if your cron job is performing cleanup, and temporary files are deleted before the installation is finished. Oracle recommends that you complete installation before daily cron jobs are run, or disable daily cron jobs that perform cleanup until after the installation is completed.
Obtain Your My Oracle Support account information	During installation, you require a My Oracle Support user name and password to configure security updates, download software updates, and other installation tasks. You can register for My Oracle Support at the following URL: https://support.oracle.com/

Table 1-8 (Cont.) Oracle Universal Installer Checklist for Oracle Grid Infrastructure Installation

Check	Task
Check running Oracle processes, and shut down processes if necessary	<ul style="list-style-type: none"> • On a node with a single-instance database not using Oracle ASM: You do not need to shut down the database while you install Oracle Grid Infrastructure. • On a node with a single-instance Oracle Database using Oracle ASM: Stop the existing Oracle ASM instances. The Oracle ASM instances are restarted during installation. • On an Oracle RAC Database node: This installation requires an upgrade of Oracle Clusterware, as Oracle Clusterware is required to run Oracle RAC. As part of the upgrade, you must shut down the database one node at a time as the rolling upgrade proceeds from node to node.

2

Checking and Configuring Server Hardware for Oracle Grid Infrastructure

Verify that servers where you install Oracle Grid Infrastructure meet the minimum requirements for installation.

This section provides minimum server requirements to complete installation of Oracle Grid Infrastructure. It does not provide system resource guidelines, or other tuning guidelines for particular workloads.

- [Logging In to a Remote System Using X Window System](#)
Use this procedure to run Oracle Universal Installer (OUI) by logging on to a remote system where the runtime setting prohibits logging in directly to a graphical user interface (GUI).
- [Checking Server Hardware and Memory Configuration](#)
Use this procedure to gather information about your server configuration.

Logging In to a Remote System Using X Window System

Use this procedure to run Oracle Universal Installer (OUI) by logging on to a remote system where the runtime setting prohibits logging in directly to a graphical user interface (GUI).

OUI is a graphical user interface (GUI) application. On servers where the runtime settings prevent GUI applications from running, you can redirect the GUI display to a client system connecting to the server.



Note:

If you log in as another user (for example, `oracle` or `grid`), then repeat this procedure for that user as well.

1. Start an X Window System session. If you are using an X Window System terminal emulator from a PC or similar system, then you may need to configure security settings to permit remote hosts to display X applications on your local system.
2. Enter a command using the following syntax to enable remote hosts to display X applications on the local X server:

```
# xhost + RemoteHost
```

RemoteHost is the fully qualified remote host name. For example:

```
# xhost + somehost.example.com  
somehost.example.com being added to the access control list
```

3. If you are not installing the software on the local system, then use the `ssh` command to connect to the system where you want to install the software:

```
# ssh -Y RemoteHost
```

RemoteHost is the fully qualified remote host name. The `-Y` flag ("yes") enables remote clients to have full access to the original server display. For example:

```
# ssh -Y somehost.example.com
```

4. If you are not logged in as the `root` user, and you are performing configuration steps that require `root` user privileges, then switch the user to `root`.

 **Note:**

For more information about remote login using X Window System, refer to your X server documentation, or contact your X server vendor or system administrator. Depending on the X server software that you are using, you may have to complete the tasks in a different order.

Checking Server Hardware and Memory Configuration

Use this procedure to gather information about your server configuration.

1. Use the following command to determine physical RAM size on the server:

```
# grep MemTotal /proc/meminfo
```

If the size of the physical RAM installed in the system is less than the required size, then you must install more memory before continuing.

2. Determine the size of the configured swap space:

```
# grep SwapTotal /proc/meminfo
```

If necessary, see your operating system documentation for information about how to configure additional swap space.

3. Determine the amount of space available in the `/tmp` directory:

```
# df -h /tmp
```

If the free space available in the `/tmp` directory is less than what is required, then complete one of the following steps:

- Delete unused files from the `/tmp` directory to meet the disk space requirement.

 **Note:**

If you perform this step after installing Oracle software, then do not remove `/tmp/.oracle` or `/var/tmp/.oracle` directories or their files.

- When you set the Oracle user's environment, also set the `TMP` and `TMPDIR` environment variables to the directory you want to use instead of `/tmp`.

4. Determine the amount of free RAM and disk swap space on the system:

```
# free
```

5. Determine if the system architecture can run the software:

```
# uname -m
```

Verify that the processor architecture matches the Oracle software release to install. For example, you should see the following for a x86-64 bit system:

```
x86_64
```

If you do not see the expected output, then you cannot install the software on this system.

6. Verify that shared memory (`/dev/shm`) is mounted properly with sufficient size:

```
df -h /dev/shm
```

The `df-h` command displays the filesystem on which `/dev/shm` is mounted, and also displays in GB the total size and free size of shared memory.

3

Automatically Configuring Oracle Linux with Oracle Database Preinstallation RPM

Use Oracle Database Preinstallation RPM to simplify operating system configuration in preparation for Oracle software installations.

Oracle recommends that you install Oracle Linux and use Oracle Database Preinstallation RPM to configure your operating systems for Oracle Database and Oracle Grid Infrastructure installations.

- [About the Oracle Database Preinstallation RPM](#)
If your Linux distribution is Oracle Linux, or Red Hat Enterprise Linux, and you are an Oracle Linux support customer, then you can complete most preinstallation configuration tasks by using the Oracle Database Preinstallation RPM for your release.
- [Overview of Oracle Linux Configuration with Oracle Database Preinstallation RPM](#)
Use Oracle Database Preinstallation RPM to simplify operating system configuration, and to ensure that you have required kernel packages.
- [Installing the Oracle Database Preinstallation RPM Using ULN](#)
Use this procedure to subscribe to Unbreakable Linux Network (ULN) Oracle Linux channels for your Oracle software.
- [Installing Oracle Database Preinstallation RPM During an Oracle Linux Installation](#)
Use this procedure to install a new Oracle Linux installation and to perform system configuration with the Oracle Preinstallation RPM:
- [Installing Oracle Oracle Database Preinstallation RPM Using the Oracle Linux yum Server](#)
Install Oracle Linux and configure your Oracle Linux installation for security errata or bug fix updates using the Oracle Linux yum server.
- [Configure Additional Operating System Features](#)
Oracle recommends that you configure your operating system before starting installation with additional features, such as IPMI or additional programming environments.

About the Oracle Database Preinstallation RPM

If your Linux distribution is Oracle Linux, or Red Hat Enterprise Linux, and you are an Oracle Linux support customer, then you can complete most preinstallation configuration tasks by using the Oracle Database Preinstallation RPM for your release.

Oracle Database Preinstallation RPMs are available from the Oracle Linux Network or available on the Oracle Linux DVDs. Using the Oracle Database Preinstallation RPM is not required, but Oracle recommends you use it to save time in setting up your cluster servers.

When installed, the Oracle Database Preinstallation RPM does the following:

- Automatically downloads and installs any additional RPM packages needed for installing Oracle Grid Infrastructure and Oracle Database, and resolves any dependencies
- Creates an `oracle` user, and creates the `oraInventory` (`oinstall`) and OSDBA (`dba`) `oper`, `backupdba`, `dgdba`, `racdba`, and `kmdba` groups for that user

- As needed, sets `sysctl.conf` settings, system startup parameters, and driver parameters to values based on recommendations from the Oracle Database Preinstallation RPM program
- Sets hard and soft resource limits
- Sets other recommended parameters, depending on your kernel version
- Sets `numa=off` in the kernel for Linux x86_64 machines.
- Sets `transparent_hugepages=madvise`

Configure Oracle Database Preinstallation RPM only once on your operating system when you install Oracle Database or Oracle Grid Infrastructure for the first time on your system. For subsequent installations on the same system, do not install Oracle Database Preinstallation RPM again.

Do not install Oracle Database Preinstallation RPM on Oracle Engineered Systems, such as Oracle Exadata Database Machine. Oracle Engineered Systems include integrated system software that contain the required version of the operating system kernel and all software packages.

 **Note:**

- The Oracle Database Preinstallation RPM designated for each Oracle Database release sets kernel parameters and resource limits only for the user account `oracle`. To use multiple software account owners, you must perform system configuration for other accounts manually.
- The Oracle Database Preinstallation RPM installs the X11 client libraries, but it does not install the X Window System server packages. To use graphical user interfaces such as OUI, configuration assistants, and Oracle Enterprise Manager, set the display to a system with X Window System server packages.

Overview of Oracle Linux Configuration with Oracle Database Preinstallation RPM

Use Oracle Database Preinstallation RPM to simplify operating system configuration, and to ensure that you have required kernel packages.

Oracle recommends that you install Oracle Linux and use Oracle Database Preinstallation RPM to configure your operating systems for Oracle Database and Oracle Grid Infrastructure installations.

Configure Oracle Database Preinstallation RPM only once on your operating system when you install Oracle Database or Oracle Grid Infrastructure for the first time on your system. For subsequent installations on the same system, do not install Oracle Database Preinstallation RPM again.

Do not install Oracle Database Preinstallation RPM on Oracle Engineered Systems, such as Oracle Exadata Database Machine. Oracle Engineered Systems include integrated system software that contain the required version of the operating system kernel and all software packages.

The Oracle Database Preinstallation RPM for your Oracle Linux distributions and database release automatically installs any additional packages needed for installing Oracle Grid

Infrastructure and Oracle Database, and configures your server operating system automatically, including setting kernel parameters and other basic operating system requirements for installation. For more information about Oracle Linux and Oracle Database Preinstallation RPM, refer to:

<http://docs.oracle.com/en/operating-systems/linux.html>

Configuring a server using Oracle Linux and the Oracle Database Preinstallation RPM consists of the following steps:

1. Install Oracle Linux.
2. Register your Linux distribution with Oracle Unbreakable Linux Network (ULN) or download and configure the yum repository for your system using the Oracle Linux yum server for your Oracle Linux release.
3. Install the Oracle Database Preinstallation RPM with the RPM for your Oracle Grid Infrastructure and Oracle Database releases, and update your Linux release.
4. Create role-allocated groups and users with identical names and ID numbers.
5. Complete network interface configuration for each cluster node candidate.
6. Complete system configuration for shared storage access as required for each standard or core node cluster candidate.

After these steps are complete, you can proceed to install Oracle Grid Infrastructure and Oracle Database.

Installing the Oracle Database Preinstallation RPM Using ULN

Use this procedure to subscribe to Unbreakable Linux Network (ULN) Oracle Linux channels for your Oracle software.

To obtain Unbreakable Linux Network (ULN) support, subscribe to Oracle Linux channels, and to add the Oracle Linux channel that distributes the Oracle Database Preinstallation RPM:

1. Download the Oracle Linux ISO from one of the following websites:

- Oracle yum

<https://yum.oracle.com/oracle-linux-isos.html>

- Oracle Software Delivery Cloud website:

<https://edelivery.oracle.com/linux>

Note:

Ensure that you use the latest available update release for Oracle Linux.

2. Register your server with Unbreakable Linux Network (ULN). By default, you are registered for the Oracle Linux Latest channel for your operating system and hardware.

[Managing Software in Oracle Linux](#)

3. Log in to Unbreakable Linux Network:

<https://linux.oracle.com>

4. Start a terminal session and enter the following command as `root`:
 - Oracle Linux 8 and Oracle Linux 9

```
# dnf install oracle-database-preinstall-23ai
```

 **Note:**

Use the `-y` option if you want `dnf` to skip the package confirmation prompt.

You should see output indicating that you have subscribed to the Oracle Linux channel, and that packages are being installed.

The Oracle Database Preinstallation RPM automatically creates a standard (not role-allocated) Oracle installation owner and groups, and sets up other kernel configuration settings as required for Oracle installations.

5. Check the RPM log file to review the system configuration changes. For example:

```
/var/log/oracle-database-preinstall-23ai/backup/timestamp/orakernel.log
```

6. Repeat steps 1 through 4 on all other servers in your cluster.

If you have a premier support subscription, you can enable Ksplice to provide zero downtime patching. Refer to the Ksplice User's Guide for installation instructions:

<https://docs.oracle.com/en/operating-systems/oracle-linux/ksplince-user/>

Installing Oracle Database Preinstallation RPM During an Oracle Linux Installation

Use this procedure to install a new Oracle Linux installation and to perform system configuration with the Oracle Preinstallation RPM:

1. Obtain Oracle Linux by downloading disk images
 - Oracle yum

<https://yum.oracle.com/oracle-linux-isos.html>

- Oracle Software Delivery Cloud website:

<https://edelivery.oracle.com/linux>

 **Note:**

Ensure that you use the latest available update release for Oracle Linux.

2. Start the Oracle Linux installation and respond to installation screens with values appropriate for your environment.

3. Review the first software selection screen, which lists task-specific software options. At the bottom of the screen, there is an option to customize now or customize later. Select **Customize now**, and click **Next**.
4. On Oracle Linux, select **Servers** on the left of the screen and **System administration tools** on the right of the screen (options may vary between releases).

The Packages in System Tools window opens.

5. Select the Oracle Database Preinstallation RPM package box from the package list. For example, select a package similar to the following:

- For Oracle Linux 8:

```
oracle-database-preinstall-23ai-1.0-2.el8.x86_64.rpm
```

- For Oracle Linux 9:

```
oracle-database-preinstall-23ai-1.0-2.el9.x86_64.rpm
```

If you do not have an Oracle Database Preinstallation RPM package option that is current for your Oracle Database release, because you are using an Oracle Linux installation that is previous to your Oracle Database and Oracle Grid Infrastructure release, then install the RPM for your release manually after completing the operating system installation.

6. Close the optional package window and click **Next**.
7. Complete the other screens to finish the Oracle Linux installation.

Oracle Linux automatically creates a standard (not role-allocated) Oracle installation owner and groups, and sets up other kernel configuration settings as required for Oracle installations.

8. Repeat steps 2 through 6 on all other cluster member nodes.

Installing Oracle Database Preinstallation RPM Using the Oracle Linux yum Server

Install Oracle Linux and configure your Oracle Linux installation for security errata or bug fix updates using the Oracle Linux yum server.

1. Refer to the official Oracle Linux documentation to install Oracle Linux:
 - Oracle Linux 8
[Installing Oracle Linux 8](#)
 - Oracle Linux 9
[Installing Oracle Linux 9](#)
 - [Managing Software in Oracle Linux](#)
2. After you have completed your Oracle Linux installation, run the command `yum update` as needed to obtain the most current security errata and bug fixes for your Oracle Linux installation.
3. Restart your system.
4. Start a terminal session and enter the following command as `root`:

- Oracle Linux 8 and Oracle Linux 9

```
# dnf install oracle-database-preinstall-23ai
```

 **Note:**

Use the `-y` option if you want `yum` to skip the package confirmation prompt.

You should see output indicating that you have subscribed to the Oracle Linux channel, and that packages are being installed.

The Oracle Database Preinstallation RPM automatically creates a standard (not role-allocated) Oracle installation owner and groups and sets up other kernel configuration settings as required for Oracle installations. If you plan to use job-role separation, then create the extended set of database users and groups depending on your requirements.

Configure Additional Operating System Features

Oracle recommends that you configure your operating system before starting installation with additional features, such as IPMI or additional programming environments.

Review the preinstallation chapters to ensure that you have completed configuration as needed for the features you want.

4

Configuring Operating Systems for Oracle Grid Infrastructure on Linux

Complete operating system configuration requirements and checks for Linux operating systems before you start installation.

- [Guidelines for Linux Operating System Installation](#)
Operating system guidelines to be aware of before proceeding with an Oracle installation.
- [Reviewing Operating System and Software Upgrade Best Practices](#)
These topics provide general planning guidelines and platform-specific information about upgrades and migration.
- [Reviewing Operating System Security Common Practices](#)
Secure operating systems are an important basis for general system security.
- [About Installation Fixup Scripts](#)
Oracle Universal Installer detects when the minimum requirements for an installation are not met, and creates shell scripts, called fixup scripts, to finish incomplete system configuration steps.
- [About Automatic Self Correction](#)
Automatic Self Correction feature provides resiliency to Oracle Grid Infrastructure by automatically identifying and correcting without user intervention for any fixable configuration issues found within the cluster.
- [About Operating System Requirements](#)
Depending on the products that you intend to install, verify that you have the required operating system kernel and packages installed.
- [Operating System Requirements for x86-64 Linux Platforms](#)
The Linux distributions and packages listed in this section are supported for this release on x86-64.
- [Additional Drivers and Software Packages for Linux](#)
Information about optional drivers and software packages.
- [Checking Kernel and Package Requirements for Linux](#)
Verify your kernel and packages to see if they meet minimum requirements for installation.
- [Setting Clock Source for VMs on Linux x86-64](#)
Oracle recommends that you set the clock source to `tsc` for better performance in virtual environments (VM) on Linux x86-64.
- [Installing the `cvuqdisk` RPM for Linux](#)
If you do not use an Oracle Database Preinstallation RPM, and you want to use the Configuration Verification Utility, then you must install the `cvuqdisk` RPM.
- [Reviewing HugePages Memory Allocation](#)
Review this information if your operating system has HugePages enabled.
- [Setting Transparent HugePages to `madvise`](#)
Transparent HugePages memory is enabled by default with Oracle Linux. However, for optimal performance, Oracle recommends that you set Transparent HugePages to `madvise` on all Oracle Database servers UEK7 and later kernels and not disable Transparent HugePages as was recommended in prior releases.

- [Enabling the Name Service Cache Daemon](#)
To allow Oracle Clusterware to better tolerate network failures with NAS devices or NFS mounts, enable the Name Service Cache Daemon (`nscd`).
- [Verifying the Disk I/O Scheduler on Linux 8 and Later Systems](#)
Disk I/O schedulers reorder, delay, or merge requests for disk I/O to achieve better throughput and lower latency.
- [Using Automatic SSH Configuration During Installation](#)
To install Oracle software, configure secure shell (SSH) connectivity between all cluster member nodes.
- [Setting Network Time Protocol for Cluster Time Synchronization](#)
You can use operating system configured network time protocol (NTP) such as `chronyd` or `ntpd` for time synchronization.
- [Verifying Digital Signature and Integrity of Installation Archive Files](#)
Starting with Oracle Database 23ai, Oracle digitally signs the installation archive files with Oracle certificates to ensure the integrity of the packages before you deploy them in your environments.

Guidelines for Linux Operating System Installation

Operating system guidelines to be aware of before proceeding with an Oracle installation.

This section provides information about installing a supported Linux distribution. Complete the minimum hardware configuration before you install the operating system.

- [Completing a Minimal or Default Linux Installation](#)
You must perform either a minimal or default Linux installation.
- [About Oracle Linux with the Unbreakable Enterprise Kernel](#)
The Unbreakable Enterprise Kernel for Oracle Linux provides the latest innovations from upstream development to customers who run Oracle Linux in the data center.
- [Configuring HugePages on Linux](#)
HugePages is a feature integrated into the Linux kernel. For Oracle Database, using HugePages reduces the operating system maintenance of page states and increases Translation Lookaside Buffer (TLB) hit ratio.
- [Restrictions for HugePages and Transparent HugePages Configurations](#)
Review the HugePages and Transparent HugePages guidelines discussed in this section.

Related Topics

- [Oracle Linux Operating System Documentation](#)
- [About the Oracle Database Preinstallation RPM](#)
If your Linux distribution is Oracle Linux, or Red Hat Enterprise Linux, and you are an Oracle Linux support customer, then you can complete most preinstallation configuration tasks by using the Oracle Database Preinstallation RPM for your release.

Completing a Minimal or Default Linux Installation

You must perform either a minimal or default Linux installation.

To complete a minimal Linux installation, select one of the minimal installation options.

A minimal Linux installation option is either a custom installation where you select the **Minimal** option from Package Group Selection, or where you deselect all packages except for the Base pack. A minimal Linux installation lacks many RPMs required for database installation, so you

must use an RPM package for your Oracle Linux release to install the required packages. The package you use depends on your Linux release, and your support status with Unbreakable Linux Network (ULN).

If you do not install the Oracle Database Preinstallation RPM, then Oracle recommends that you install your Linux operating system with the default software packages (RPMs).

A default Linux installation includes most of the required packages and helps you limit manual verification of package dependencies. Oracle recommends that you do not customize the RPMs during installation.

Refer to the official Oracle Linux documentation for more information about installing Oracle Linux:

- Oracle Linux 8:
[Installing Oracle Linux 8](#)
- Oracle Linux 9:
[Installing Oracle Linux 9](#)
- [Managing Software in Oracle Linux](#)

About Oracle Linux with the Unbreakable Enterprise Kernel

The Unbreakable Enterprise Kernel for Oracle Linux provides the latest innovations from upstream development to customers who run Oracle Linux in the data center.

The Unbreakable Enterprise Kernel is included and enabled by default in Oracle Linux kernels. It is based on a recent stable mainline development Linux kernel, and also includes optimizations developed in collaboration with Oracle Database, Oracle middleware, and Oracle hardware engineering teams to ensure stability and optimal performance for the most demanding enterprise workloads.

Oracle highly recommends deploying the Unbreakable Enterprise Kernel in your Oracle Linux environment, especially if you run enterprise applications. However, using Unbreakable Enterprise Kernel is optional. If you require strict Red Hat Enterprise Linux (RHEL) kernel compatibility, then Oracle Linux also includes a kernel compatible with the RHEL Linux kernel, compiled directly from the RHEL source code.

You can obtain more information about the Unbreakable Enterprise Kernel for Oracle Linux at the following URL:

<https://www.oracle.com/linux/>

The Unbreakable Enterprise Kernel for Oracle Linux is the standard kernel used with Oracle products. The build and QA systems for Oracle Database and other Oracle products use the Unbreakable Enterprise Kernel for Oracle Linux exclusively. The Unbreakable Enterprise Kernel for Oracle Linux is also the kernel used in Oracle Exadata systems. Unbreakable Enterprise Kernel for Oracle Linux is used in all benchmark tests on Linux in which Oracle participates, as well as in the Oracle Database Preinstallation RPM program for x86-64.

Oracle Ksplice, which is part of Oracle Linux, updates the Linux operating system (OS) kernel, while it is running, without requiring restarts or any interruption. Ksplice is available only with Oracle Linux.

Configuring HugePages on Linux

HugePages is a feature integrated into the Linux kernel. For Oracle Database, using HugePages reduces the operating system maintenance of page states and increases Translation Lookaside Buffer (TLB) hit ratio.



Note:

HugePages support is available in kernels built with the `CONFIG_HUGETLBFS` and `CONFIG_HUGETLB_PAGE` configuration options.

Oracle recommends that you reserve a minimum of 30 percent of the total memory for standard pages and not more than 70 percent of the total memory for HugePages.

Ensure that you have created the Oracle Database software owner (oracle) user accounts and all its groups. For more information see, [Automatically Configuring Oracle Linux with Oracle Database Preinstallation RPM](#) or [Creating an Oracle Software Owner User](#).

Enabling Using HugePages

Perform these steps to enable HugePages on Linux:

1. Check if the kernel supports HugePages:

```
$ grep Huge /proc/meminfo
```

2. Edit the `memlock` setting in the `/etc/security/limits.conf` file.

Specify the `memlock` setting in KB. Set the maximum locked memory limit to at least 90 percent of the current RAM when you enable HugePages memory and at least to 3145728 KB (3 GB) if you disable HugePages. For example, if you have 64 GB RAM, then add the following entries to increase the maximum locked-in-memory address space:

```
* soft memlock 60397977
* hard memlock 60397977
```

You can also set the `memlock` value higher than your SGA requirements.

3. Log in as the `oracle` user again and run the `ulimit -l` command to verify the new `memlock` setting:

```
$ ulimit -l
60397977
```

4. Run the following command to display the value of the `Hugepagesize` variable:

```
$ grep Hugepagesize /proc/meminfo
```

5. Determine the `gid` or `oracle` user group ID value:

```
# id oracle
```

The output is similar to the following:

```
uid=54321(oracle) gid=54321(oinstall) groups=54321(oinstall),54322(dba),  
54323(oper),54324(backupdba),54325(dgdba),54326(kmdba),54327(asmdba),54330(  
racdba)
```

Note the value of `gid`.

6. Set the `vm.hugetlb_shm_group` kernel parameter value to the `gid` value:

```
# sysctl -w vm.hugetlb_shm_group=gid
```

where `gid` is the `oracle` user group ID. For example, value of `gid=54321`.

To ensure that this value is available even after the system restarts, add the following entry to the `/etc/sysctl.d/99-hugetlb-shm-group.conf` file that contains this setting.

```
vm.hugetlb_shm_group=gid
```

Configuring the Capacity for HugePages

To configure the required number of HugePages for your databases, perform this step after you complete the Oracle Database installation and create your databases.

1. Complete the following procedure to create a script that computes recommended values for HugePages configuration for the current shared memory segments:

- a. Create a text file `hugepages_settings.sh`

See [My Oracle Support note 401749.1](#) to create the `hugepages_settings.sh` script.

- b. Change the permission of the `hugepages_settings.sh` file:

```
$ chmod +x hugepages_settings.sh
```

2. Run the `hugepages_settings.sh` script to compute values for the HugePages configuration.

```
$ ./hugepages_settings.sh
```

Note:

Before you run this script, ensure that all the databases that use hugepages run.

3. Set the following kernel parameter, where `value` is the HugePages value that you determined in Step 2:

```
# sysctl -w vm.nr_hugepages=value
```


4. To ensure that HugePages is allocated after the system restarts, add the following entry to the `/etc/sysctl.d/99-nr_hugepages.conf` file, where `value` is the HugePages value that you determined in Step 2:

```
vm.nr_hugepages=value
```

 **Note:**

If you cannot set your HugePages allocation using `nr_hugepages`, then your available memory may be fragmented. Restart your server for the HugePages allocation to take effect.

5. Run the following command to check the available HugePages:

```
$ grep Huge /proc/meminfo
```

6. Restart the instances.
7. Run the following command to check the available HugePages (1 or 2 pages free):

```
$ grep Huge /proc/meminfo
```

Restrictions for HugePages and Transparent HugePages Configurations

Review the HugePages and Transparent HugePages guidelines discussed in this section.

For optimal performance, Oracle recommends that you set Transparent HugePages to `madvise` on all Oracle Database servers UEK7 and later kernels and not disable Transparent HugePages as was recommended in prior releases.

Oracle continues to recommend using standard HugePages for Linux. Transparent HugePages memory is enabled by default.

If you install Oracle Database Preinstallation RPM, then it sets Transparent HugePages to `madvise` on all Oracle Database servers UEK7 and later kernels.

Transparent Hugepages are similar to standard HugePages. However, while standard HugePages allocate memory at startup, Transparent Hugepages memory uses the `khugepaged` thread in the kernel to allocate memory dynamically during runtime, using swappable HugePages.

HugePages allocates non-swappable memory for large page tables using memory-mapped files. HugePages are not enabled by default. If you enable HugePages, then you should deduct the memory allocated to HugePages from the available RAM before calculating swap space. Refer to your distribution documentation and to Oracle Technology Network and My Oracle Support for more information.

Reviewing Operating System and Software Upgrade Best Practices

These topics provide general planning guidelines and platform-specific information about upgrades and migration.

- [General Upgrade Best Practices](#)
Be aware of these guidelines as a best practice before you perform an upgrade.
- [New Server Operating System Upgrade Option](#)
You can upgrade your operating system by installing a new operating system on a server, and then migrating your database either manually, or by using Export/Import method.
- [Upgrading Operating System for an Oracle Grid Infrastructure Server](#)
Complete this procedure on each Oracle Grid Infrastructure node to upgrade the operating system for an Oracle Grid Infrastructure server.
- [Oracle ASM Upgrade Notifications](#)
Understand Oracle ASM upgrade options and restrictions.

General Upgrade Best Practices

Be aware of these guidelines as a best practice before you perform an upgrade.

If you have an existing Oracle Database installation, then do the following:

- Record the version numbers, patches, and other configuration information
- Review upgrade procedures for your existing installation
- Review Oracle Database upgrade documentation before proceeding with installation, to decide how you want to proceed

Caution:

Always create a backup of existing databases before starting any configuration change.

Refer to *Oracle Database Upgrade Guide* for more information about required software updates, pre-upgrade tasks, post-upgrade tasks, compatibility, and interoperability between different releases.

Related Topics

- [Oracle Database Upgrade Guide](#)

New Server Operating System Upgrade Option

You can upgrade your operating system by installing a new operating system on a server, and then migrating your database either manually, or by using Export/Import method.

Note:

Confirm that the server operating system is supported, and that kernel and package requirements for the operating system meet or exceed the minimum requirements for the Oracle Database release to which you want to migrate.

Manual, Command-Line Copy for Migrating Data and Upgrading Oracle Database

You can copy files to the new server and upgrade it manually. If you use this procedure, then you cannot use Oracle Database Upgrade Assistant. However, you can revert to your existing database if you encounter upgrade issues.

 **Note:**

Database Upgrade Assistant (DBUA) is desupported. Oracle recommends using AutoUpgrade to upgrade your database.

1. Copy the database files from the computer running the previous operating system to the one running the new operating system.
2. Re-create the control files on the computer running the new operating system.
3. Manually upgrade the database using command-line scripts and utilities.

 **See Also:**

Oracle Database Upgrade Guide to review the procedure for upgrading the database manually, and to evaluate the risks and benefits of this option

Export/Import Method for Migrating Data and Upgrading Oracle Database

You can install the operating system on the new server, install the new Oracle Database release on the new server, and then use Oracle Data Pump Export and Import utilities to migrate a copy of data from your current database to a new database in the new release. Oracle Data Pump Export and Import are recommended for higher performance and to ensure support for new data types.

 **See Also:**

Oracle Database Upgrade Guide to review the Export/Import method for migrating data and upgrading Oracle Database

Upgrading Operating System for an Oracle Grid Infrastructure Server

Complete this procedure on each Oracle Grid Infrastructure node to upgrade the operating system for an Oracle Grid Infrastructure server.

1. As the `root` user, relocate all Oracle Database services running from the current node to another node.

```
# cd Grid_home/bin
# srvctl relocate service -drain_timeout
```

2. Disable the automatic startup of Oracle High Availability Services, when the server reboots, on the first node.

```
# cd Grid_home/bin  
# ./crsctl disable crs
```

3. Shut down the Oracle Clusterware stack on the first node.

```
# ./crsctl stop crs
```

4. Update the operating system to a version that is supported for your Oracle Grid Infrastructure release.

Refer to your operating system documentation for more information about upgrading the operating system.

 **Note:**

For an operating system upgrade that results in a new root file system, you must remove the node from the cluster and add it back into the cluster.

5. Reboot your Oracle Grid Infrastructure server after the operating system upgrade is complete.

6. Update the Oracle Clusterware operating system files.

```
# ./rootcrs.sh -updateosfiles
```

7. As the `root` user, enable the automatic startup of Oracle High Availability Services, when the server reboots, on the first node.

```
# cd Grid_home/bin  
# ./crsctl enable crs
```

8. Start the Oracle Clusterware stack on the first node.

```
# ./crsctl start crs
```

9. Repeat steps 1 through 8 on all the Oracle Clusterware nodes.

Related Topics

- [Relinking Oracle Grid Infrastructure for a Cluster Binaries](#)
After installing Oracle Grid Infrastructure for a cluster, if you modify the Oracle Grid Infrastructure binaries, then you must relink the binaries on Oracle Linux 8 or earlier releases.

Oracle ASM Upgrade Notifications

Understand Oracle ASM upgrade options and restrictions.

- You can upgrade Oracle Automatic Storage Management (Oracle ASM) without shutting down an Oracle RAC database by performing a rolling upgrade either of individual nodes, or of a set of nodes in the cluster. However, if you have a single-instance database on a cluster that uses Oracle ASM, then you must shut down the single-instance database before upgrading.

- Oracle ASM is installed with Oracle Clusterware in the Oracle Grid Infrastructure home (Grid home).
- Two nodes of different releases cannot run in the cluster. If there is an outage during the rolling upgrade, then when you restart the upgrade, ensure that you start the earlier release of Oracle Grid Infrastructure and bring the Oracle ASM cluster back in the rolling migration mode.

Reviewing Operating System Security Common Practices

Secure operating systems are an important basis for general system security.

Ensure that your operating system deployment is in compliance with common security practices as described in your operating system vendor security guide.

About Installation Fixup Scripts

Oracle Universal Installer detects when the minimum requirements for an installation are not met, and creates shell scripts, called fixup scripts, to finish incomplete system configuration steps.

If Oracle Universal Installer detects an incomplete task, then it generates fixup scripts (`runfixup.sh`). You can run the fixup script and click **Fix and Check Again**. The fixup script modifies both persistent parameter settings and parameters in memory, so you do not have to restart the system.

The Fixup script does the following tasks:

- Sets kernel parameters, if necessary, to values required for successful installation, including:
 - Shared memory parameters.
 - Open file descriptor and UDP send/receive parameters.
- Creates and sets permissions on the Oracle Inventory (central inventory) directory.
- Creates or reconfigures primary and secondary group memberships for the installation owner, if necessary, for the Oracle Inventory directory and the operating system privileges groups.
- Sets shell limits, if necessary, to required values.

Note:

Using fixup scripts does not ensure that all the prerequisites for installing Oracle Database are met. You must still verify that all the preinstallation requirements are met to ensure a successful installation.

Oracle Universal Installer is fully integrated with Configuration Verification Utility (CVU) automating many prerequisite checks for your Oracle Grid Infrastructure or Oracle Real Application Clusters (Oracle RAC) installation. You can also manually perform various CVU verifications by running the `cluvfy` command.

Related Topics

- *Oracle Clusterware Administration and Deployment Guide*

About Automatic Self Correction

Automatic Self Correction feature provides resiliency to Oracle Grid Infrastructure by automatically identifying and correcting without user intervention for any fixable configuration issues found within the cluster.

The automated fixup framework of Configuration Verification Utility (CVU) identifies and corrects any configuration errors in your Oracle Clusterware environment without user intervention. CVU periodically performs verification checks and runs fixup scripts on all applicable nodes from the local node. This ensures that your environment follows the recommended prerequisites and best practices on each cluster node. If an automated correction requires a reboot of one or more cluster nodes, then an alert message is written to the CRS alert log.

Select the **Enable Automatic Self Correction** option during Oracle Grid Infrastructure installation to configure automatic select correction for your Oracle Grid Infrastructure installation.

Related Topics

- *Oracle Clusterware Administration and Deployment Guide*

About Operating System Requirements

Depending on the products that you intend to install, verify that you have the required operating system kernel and packages installed.

Requirements listed in this document are current as of the date listed on the title page.

Oracle Universal Installer performs checks on your system to verify that it meets the listed operating system package requirements. To ensure that these checks complete successfully, verify the requirements before you start OUI.

Note:

Oracle does not support running different operating system versions on cluster members, unless an operating system is being upgraded. You cannot run different operating system version binaries on members of the same cluster, even if each operating system is supported.

Operating System Requirements for x86-64 Linux Platforms

The Linux distributions and packages listed in this section are supported for this release on x86-64.

Identify the requirements for your Linux distribution, and ensure that you have a supported kernel and required packages installed before starting installation.

The platform-specific hardware and software requirements included in this guide were current when this guide was published. However, because new platforms and operating system software versions may be certified after this guide is published, review the certification matrix on the My Oracle Support website for the most up-to-date list of certified hardware platforms and operating system versions:

<https://support.oracle.com/>

- [General Guidelines for Operating System Packages](#)
Review these guidelines before you proceed with installing operating system packages.
- [Supported Oracle Linux 9 Distributions for x86-64](#)
Use the following information to check supported Oracle Linux 9 distributions:
- [Supported Oracle Linux 8 Distributions for x86-64](#)
Use the following information to check supported Oracle Linux 8 distributions:
- [Supported Red Hat Enterprise Linux 9 Distributions for x86-64](#)
Use the following information to check supported Red Hat Enterprise Linux 9 distributions:
- [Supported Red Hat Enterprise Linux 8 Distributions for x86-64](#)
Use the following information to check supported Red Hat Enterprise Linux 8 distributions:
- [Supported SUSE Linux Enterprise Server 15 Distributions for x86-64](#)
Use the following information to check supported SUSE Linux Enterprise Server 15 distributions:
- [Installing Operating System Packages](#)
Learn how to install the latest version of your Oracle Linux and SUSE Linux Enterprise Server operating system packages listed earlier.

General Guidelines for Operating System Packages

Review these guidelines before you proceed with installing operating system packages.

- Oracle recommends that you install Oracle Linux and use Oracle Database Preinstallation RPM to configure your operating systems for Oracle Database and Oracle Grid Infrastructure installations.
- The Oracle Database interactive installation requires an X Window System (for example, `libX`). The `libX` packages are not part of a default Linux installation. If you perform an installation on a system with a reduced set of packages, then you must ensure that `libX` or a similar X Window System package is installed.
- Oracle Database 12c Release 2 (12.2) and later does not require the compiler packages `gcc` and `gcc-c++` on for Oracle Database or Oracle Grid Infrastructure installations.
- These operating system requirements do not apply to Oracle Engineered Systems, such as Oracle Exadata Database Machine and Oracle Database Appliance. Oracle Engineered Systems include integrated system software that contain the required version of the operating system kernel and all software packages. Please verify that you have the minimum required Exadata image. Refer My Oracle Support note 888828.1 and 888888.1 for more information.

Related Topics

- [My Oracle Support Note 888828.1](#)
- [My Oracle Support Note 888888.1](#)

Supported Oracle Linux 9 Distributions for x86-64

Use the following information to check supported Oracle Linux 9 distributions:

Table 4-1 x86-64 Oracle Linux 9 Minimum Operating System Requirements

Item	Requirements
SSH Requirement	Ensure that OpenSSH is installed on your servers. OpenSSH is the required SSH software.
Oracle Linux 9	<p>Minimum supported versions:</p> <ul style="list-style-type: none">• Oracle Linux 9.2 with the Unbreakable Enterprise Kernel 7: 5.15.0-201.135.6.el9uek.x86_64 or later• Oracle Linux 9.2 with the Red Hat Compatible Kernel: 5.14.0-284.30.1.el9_2.x86_64 or later <p>Note: Oracle recommends that you update Oracle Linux to the latest available version and release level.</p>

Table 4-1 (Cont.) x86-64 Oracle Linux 9 Minimum Operating System Requirements

Item	Requirements
Packages for Oracle Linux 9	<p>Subscribe to the Oracle Linux 9 channel on the Unbreakable Linux Network, or configure a yum repository from the Oracle Linux yum server website, and then install the Oracle Database Preinstallation RPM, <code>oracle-database-preinstall-23ai</code>. The Oracle Database Preinstallation RPM, <code>oracle-database-preinstall-23ai</code>, automatically installs all required packages listed in the table below, their dependencies for Oracle Grid Infrastructure and Oracle Database installations, and also performs other system configuration. If you install the Oracle Database Preinstallation RPM, <code>oracle-database-preinstall-23ai</code>, then you do not have to install these packages, as the Oracle Database Preinstallation RPM automatically installs them.</p>
	<p><code>bc</code> <code>binutils</code> <code>compat-openssl11</code> <code>elfutils-libelf</code> <code>fontconfig</code> <code>glibc</code> <code>glibc-devel</code> <code>glibc-headers</code> <code>ksh</code> <code>libaio</code> <code>libasan</code> <code>liblsan</code> <code>libX11</code> <code>libXau</code> <code>libXi</code> <code>libXrender</code> <code>libXtst</code> <code>libxcrypt-compat</code> <code>libgcc</code> <code>libibverbs</code> <code>librdmacm</code> <code>libstdc++</code> <code>libxcb</code> <code>libvirt-libs</code> <code>make</code> <code>policycoreutils</code> <code>policycoreutils-python-utils</code> <code>smartmontools</code> <code>sysstat</code></p>
Optional Packages for Oracle Linux 9	<p>Based on your requirement, install the latest released versions of the following packages:</p> <p><code>ipmiutil</code> (for Intelligent Platform Management Interface) <code>libnsI2</code> (for Oracle Database Client only) <code>libnsI2-devel</code> (for Oracle Database Client only) <code>net-tools</code> (for Oracle RAC and Oracle Clusterware) <code>nfs-utils</code> (for Oracle ACFS)</p>

Supported Oracle Linux 8 Distributions for x86-64

Use the following information to check supported Oracle Linux 8 distributions:

Table 4-2 x86-64 Oracle Linux 8 Minimum Operating System Requirements

Item	Requirements
SSH Requirement	Ensure that OpenSSH is installed on your servers. OpenSSH is the required SSH software.
Oracle Linux 8	<p>Minimum supported versions:</p> <ul style="list-style-type: none"> • Oracle Linux 8.6 with the Unbreakable Enterprise Kernel 6: 5.4.17-2136.312.3.4.el8uek.x86_64 or later • Oracle Linux 8.6 with the Red Hat Compatible Kernel: 4.18.0-372.26.1.0.1.el8_6.x86_64 or later <p>Starting with Oracle Database 23ai release 23.5, the following minimum version is supported:</p> <ul style="list-style-type: none"> • Oracle Linux 8.8 with the Unbreakable Enterprise Kernel 7: 5.15.0-202.135.2.el8uek.x86_64 or later <p>Note: Oracle recommends that you update Oracle Linux to the latest available version and release level.</p>

Table 4-2 (Cont.) x86-64 Oracle Linux 8 Minimum Operating System Requirements

Item	Requirements
Packages for Oracle Linux 8	<p>Subscribe to the Oracle Linux 8 channel on the Unbreakable Linux Network, or configure a yum repository from the Oracle Linux yum server website, and then install the Oracle Database Preinstallation RPM, <code>oracle-database-preinstall-23ai</code>. The Oracle Database Preinstallation RPM, <code>oracle-database-preinstall-23ai</code>, automatically installs all required packages listed in the table below, their dependencies for Oracle Grid Infrastructure and Oracle Database installations, and also performs other system configuration. If you install the Oracle Database Preinstallation RPM, <code>oracle-database-preinstall-23ai</code>, then you do not have to install these packages, as the Oracle Database Preinstallation RPM automatically installs them.</p>
	<p><code>bc</code> <code>binutils</code> <code>compat-openssl10</code> <code>elfutils-libelf</code> <code>fontconfig</code> <code>glibc</code> <code>glibc-devel</code> <code>ksh</code> <code>libaio</code> <code>libXrender</code> <code>libX11</code> <code>libXau</code> <code>libXi</code> <code>libXtst</code> <code>libgcc</code> <code>libstdc++</code> <code>libxcb</code> <code>libibverbs</code> <code>libasan</code> <code>liblsan</code> <code>librdmacm</code> <code>make</code> <code>policycoreutils</code> <code>policycoreutils-python-utils</code> <code>smartmontools</code> <code>sysstat</code></p>
Optional Packages for Oracle Linux 8	<p>Based on your requirement, install the latest released versions of the following packages:</p> <p><code>ipmiutil</code> (for Intelligent Platform Management Interface) <code>libnsI2</code> (for Oracle Database Client only) <code>libnsI2-devel</code> (for Oracle Database Client only) <code>net-tools</code> (for Oracle RAC and Oracle Clusterware) <code>nfs-utils</code> (for Oracle ACFS)</p>

Supported Red Hat Enterprise Linux 9 Distributions for x86-64

Use the following information to check supported Red Hat Enterprise Linux 9 distributions:

Table 4-3 x86-64 Red Hat Enterprise Linux 9 Minimum Operating System Requirements

Item	Requirements
SSH Requirement	Ensure that OpenSSH is installed on your servers. OpenSSH is the required SSH software.
Red Hat Enterprise Linux 9	Minimum supported version: Red Hat Enterprise Linux 9.2: 5.14.0-284.30.1.el9_2.x86_64 or later
Packages for Red Hat Enterprise Linux 9	Install the latest released versions of the following packages: bc binutils compat-openssl11 elfutils-libelf fontconfig glibc glibc-devel glibc-headers ksh libaio libasan liblsan libX11 libXau libXi libXrender libXtst libxcrypt-compat libgcc libibverbs librdmacm libstdc++ libxcb libvirt-libs make policycoreutils policycoreutils-python-utils smartmontools sysstat
Optional Packages for Red Hat Enterprise Linux 9	Based on your requirement, install the latest released versions of the following packages: ipmiutil (for Intelligent Platform Management Interface) libns12 (for Oracle Database Client only) libns12-devel (for Oracle Database Client only) net-tools (for Oracle RAC and Oracle Clusterware) nfs-utils (for Oracle ACFS)

Supported Red Hat Enterprise Linux 8 Distributions for x86-64

Use the following information to check supported Red Hat Enterprise Linux 8 distributions:

Table 4-4 x86-64 Red Hat Enterprise Linux 8 Minimum Operating System Requirements

Item	Requirements
SSH Requirement	Ensure that OpenSSH is installed on your servers. OpenSSH is the required SSH software.
Red Hat Enterprise Linux 8	Minimum supported version: Red Hat Enterprise Linux 8.6: 4.18.0-372.26.1.0.1.el8_6.x86_64 or later
Packages for Red Hat Enterprise Linux 8	Install the latest released versions of the following packages: bc binutils compat-openssl10 elfutils-libelf fontconfig glibc glibc-devel ksh libaio libXrender libX11 libXau libXi libXtst libgcc libstdc++ libxcb libibverbs libasan liblsan librdmacm make policycoreutils policycoreutils-python-utils smartmontools sysstat
Optional Packages for Red Hat Enterprise Linux 8	Based on your requirement, install the latest released versions of the following packages: ipmiutil (for Intelligent Platform Management Interface) libnsl2 (for Oracle Database Client only) libnsl2-devel (for Oracle Database Client only) net-tools (for Oracle RAC and Oracle Clusterware) nfs-utils (for Oracle ACFS)

Supported SUSE Linux Enterprise Server 15 Distributions for x86-64

Use the following information to check supported SUSE Linux Enterprise Server 15 distributions:

Table 4-5 x86-64 SUSE Linux Enterprise Server 15 Minimum Operating System Requirements

Item	Requirements
SSH Requirement	Ensure that OpenSSH is installed on your servers. OpenSSH is the required SSH software.
SUSE Linux Enterprise Server	Minimum supported version: SUSE Linux Enterprise Server 15 SP5 (x86_64): 5.14.21-150500.53-default or later
Packages for SUSE Linux Enterprise Server 15	Install the latest released versions of the following packages: bc glibc gcc8 insserv-compat libaio-devel libaio1 libX11-6 libXau6 libXext-devel libXext6 libXi-devel libXi6 libXrender-devel libXrender1 libXtst6 libcap-ng-utils libcap-ng0 libcap-progs libcap1 libcap2 libelf1 libgcc_s1 libjpeg8 libpcap1 libpcre1 libpng16 libstdc++6 libgfortran4 mksh make pixz smartmontools sysstat xorg-x11-libs

Table 4-5 (Cont.) x86-64 SUSE Linux Enterprise Server 15 Minimum Operating System Requirements

Item	Requirements
Optional Packages for SUSE Linux Enterprise Server 15	Based on your requirement, install the latest released versions of the following packages: ipmiutil (for Intelligent Platform Management Interface) net-tools (for Oracle RAC and Oracle Clusterware)

Installing Operating System Packages

Learn how to install the latest version of your Oracle Linux and SUSE Linux Enterprise Server operating system packages listed earlier.

You must install the latest version of your operating system packages from the respective operating system vendor repository by using a package manager like DNF, YUM or YaST depending on your operating system.

Ensure that the appropriate channel or repository is enabled to include these packages.

For example:

On Oracle Linux or Red Hat Enterprise Linux, to install the latest `bc` package, run one of the following command:

- `# dnf install bc`

(or)

- `# yum install bc`

On SUSE Linux Enterprise Server, to install the latest `bc` package using YaST, run the following command:

```
$ yast --install bc
```

Additional Drivers and Software Packages for Linux

Information about optional drivers and software packages.

You are not required to install additional drivers and packages, but you may choose to install or configure these drivers and packages.

- [Installing PAM for Login Authentication on Linux](#)
Pluggable Authentication Modules (PAM) is a system of libraries that handle user authentication tasks for applications.
- [Installing OCFS2](#)
You can use Oracle Cluster File System 2 (OCFS2) with Oracle Grid Infrastructure. However, you are not required to use OCFS2.

- [Installation Requirements for ODBC and LDAP](#)
Review these topics to install Open Database Connectivity (ODBC) and Lightweight Directory Access Protocol (LDAP).
- [Installing Oracle Messaging Gateway](#)
Oracle Messaging Gateway is installed with Enterprise Edition of Oracle Database. However, you may require a CSD or Fix Packs.
- [Installation Requirements for Programming Environments for Linux](#)
Review the following section to install programming environments:
- [Installation Requirements for Web Browsers](#)
Web browsers are required only if you intend to use Oracle Enterprise Manager Cloud Control. Web browsers must support JavaScript, and the HTML 4.0 and CSS 1.0 standards.

Installing PAM for Login Authentication on Linux

Pluggable Authentication Modules (PAM) is a system of libraries that handle user authentication tasks for applications.

On Linux, external scheduler jobs require PAM. Oracle strongly recommends that you install the latest Linux-PAM library for your Linux distribution.

Use a package management system (`yum`, `up2date`, `YaST`) for your distribution to install the latest `pam` (Pluggable Authentication Modules for Linux) library.

Installing OCFS2

You can use Oracle Cluster File System 2 (OCFS2) with Oracle Grid Infrastructure. However, you are not required to use OCFS2.

OCFS2 is a POSIX-compliant general purpose shared disk cluster file system for Linux. OCFS2 is supported for this release only with Oracle Linux.

An OCFS2 installation consists of two parts, the kernel module and the tools module. The supported version of the OCFS2 kernel module depends on the version of Unbreakable Enterprise Kernel available with Oracle Linux.

1. Run the following command to install the latest version of the OCFS2 kernel module:

```
# dnf install kernel-uek
```

2. Run the following command to install the OCFS2 tools module after you install the OCFS2 kernel module:

```
# dnf install ocfs2-tools
```

Note:

- Each cluster node should run the same version of OCFS2 modules and a compatible version of Unbreakable Enterprise Kernel.
- OCFS2 is not supported on Linux for ARM (aarch64).

<https://oss.oracle.com/projects/ocfs2/>

Installation Requirements for ODBC and LDAP

Review these topics to install Open Database Connectivity (ODBC) and Lightweight Directory Access Protocol (LDAP).

- [About ODBC Drivers and Oracle Database](#)
Open Database Connectivity (ODBC) is a set of database access APIs that connect to the database, prepare, and then run SQL statements on the database.
- [Installing ODBC Drivers for Linux x86-64](#)
If you intend to install Oracle's ODBC driver, then you must also install the most recent ODBC Driver Manager for Linux.
- [About LDAP and Oracle Plug-ins](#)
Lightweight Directory Access Protocol (LDAP) is an application protocol for accessing and maintaining distributed directory information services over IP networks.
- [Installing the LDAP Package](#)
LDAP is included in a default Linux operating system installation.

About ODBC Drivers and Oracle Database

Open Database Connectivity (ODBC) is a set of database access APIs that connect to the database, prepare, and then run SQL statements on the database.

An application that uses an ODBC driver can access non-uniform data sources, such as spreadsheets and comma-delimited files.

Installing ODBC Drivers for Linux x86-64

If you intend to install Oracle's ODBC driver, then you must also install the most recent ODBC Driver Manager for Linux.

Download and install the ODBC Driver Manager and Linux RPMs from the following website:

<http://www.unixodbc.org>

Review the minimum supported ODBC driver releases, and install ODBC drivers of the following or later releases for all Linux distributions:

`unixODBC-2.3.4` or later

About LDAP and Oracle Plug-ins

Lightweight Directory Access Protocol (LDAP) is an application protocol for accessing and maintaining distributed directory information services over IP networks.

You require the LDAP package if you want to use features requiring LDAP, including the Oracle Database scripts `odisrvreg` and `oidca` for Oracle Internet Directory, or `schemasync` for third-party LDAP directories.

Installing the LDAP Package

LDAP is included in a default Linux operating system installation.

If you did not perform a default Linux installation, and you intend to use Oracle scripts requiring LDAP, then use a package management system (`up2date`, `YaST`) for your distribution to install a supported LDAP package for your distribution, and install any other required packages for that LDAP package.

Installing Oracle Messaging Gateway

Oracle Messaging Gateway is installed with Enterprise Edition of Oracle Database. However, you may require a CSD or Fix Packs.

If you require a CSD or Fix Packs for IBM WebSphere MQ, then see the following website for more information:

<https://www.ibm.com/support/>



Note:

Oracle Messaging Gateway does not support the integration of Advanced Queuing with TIBCO Rendezvous on IBM: Linux on System z.

Related Topics

- *Oracle Database Advanced Queuing User's Guide*

Installation Requirements for Programming Environments for Linux

Review the following section to install programming environments:

The Oracle JDBC Oracle Call Interface (OCI) Type 2 client driver (also known as a "thick" driver) is deprecated in Oracle Database 23ai.

Most Java applications that use Open Database Connectivity (ODBC) with Oracle JDBC drivers use the Thin driver. To enable Oracle to allocate resources to better address customer requirements, Oracle is deprecating the JDBC-OCI driver.

- [Installation Requirements for Programming Environments for Linux x86-64](#)
Ensure that your system meets the requirements for the programming environment you want to configure:

Installation Requirements for Programming Environments for Linux x86-64

Ensure that your system meets the requirements for the programming environment you want to configure:

Table 4-6 Requirements for Programming Environments for Linux X86-64

Programming Environments	Support Requirements
Java Database Connectivity (JDBC) / JDBC Oracle Call Interface (JDBC OCI)	JDK 11 (Java SE Development Kit) with the JNDI extension with Oracle Java Database Connectivity.

Table 4-6 (Cont.) Requirements for Programming Environments for Linux X86-64

Programming Environments	Support Requirements
Oracle Call Interface (OCI) Oracle C++ Call Interface Pro*C/C++	Intel(R) C Intel(R) 64 Compiler Classic for applications running on Intel(R) 64, Version 2021.10.1. Oracle C++ Call Interface (OCCI) applications can be built with g++8 or the 2021.10.1 Intel C++ Compiler used with the standard template libraries of gcc8.
Oracle XML Developer's Kit (XDK)	Oracle XML Developer's Kit is supported with the same compilers as OCCI.
Pro*COBOL	<ul style="list-style-type: none"> • Micro Focus Visual COBOL for Eclipse 2.3 - Update 2 • Micro Focus Visual COBOL v6.0
Unzip and Tar	Install the latest versions of Unzip and Tar. Unzip and Tar utilities are required to extract the image files for Oracle Database and Oracle Grid Infrastructure installations and patches.

Installation Requirements for Web Browsers

Web browsers are required only if you intend to use Oracle Enterprise Manager Cloud Control. Web browsers must support JavaScript, and the HTML 4.0 and CSS 1.0 standards.

<https://support.oracle.com>

Related Topics

- *Oracle Enterprise Manager Cloud Control Basic Installation Guide*

Checking Kernel and Package Requirements for Linux

Verify your kernel and packages to see if they meet minimum requirements for installation.

1. To determine the distribution and version of Linux installed, enter one of the following commands:

```
# cat /etc/oracle-release
# cat /etc/redhat-release
# cat /etc/os-release
# lsb_release -id
```

2. To determine if the required kernel errata is installed, enter the following command:

```
# uname -r
```

The following is an example of the output this command displays on an Oracle Linux 8 system:

```
5.4.17-2011.1.2.el8uek.x86_64
```

Review the required errata level for your distribution. If the errata level is previous to the required minimum errata update, then obtain and install the latest kernel update from your Linux distributor.

3. To determine whether the required packages are installed, enter commands similar to the following:

```
# rpm -q package_name
```

Alternatively, if you require specific system architecture information, then enter the following command:

```
# rpm -qa --queryformat "%{NAME}-%{VERSION}-%{RELEASE} (%{ARCH})\n" | grep package_name
```

You can also combine a query for multiple packages, and review the output for the correct versions. For example:

```
# rpm -q binutils compat-libstdc++ gcc glibc libaio libgcc libstdc++ \  
make sysstat unixodbc
```

If a package is not installed, then install it from your Linux distribution media or download the required package version from your Linux distributor's website.

Setting Clock Source for VMs on Linux x86-64

Oracle recommends that you set the clock source to `tsc` for better performance in virtual environments (VM) on Linux x86-64.

1. As the `root` user, check if the `tsc` clock source is available on your system.

```
# cat /sys/devices/system/clocksource/clocksource0/available_clocksource  
kvm-clock tsc acpi_pm
```

2. If the `tsc` clock source is available, then set `tsc` as the current clock source.

```
# echo "tsc">/sys/devices/system/clocksource/clocksource0/  
current_clocksource
```

3. Verify that the current clock source is set to `tsc`.

```
# cat /sys/devices/system/clocksource/clocksource0/current_clocksource  
tsc
```

4. Using any text editor, append the `clocksource` directive to the `GRUB_CMDLINE_LINUX` line in the `/etc/default/grub` file to retain this clock source setting even after a reboot.

```
GRUB_CMDLINE_LINUX="rd.lvm.lv=ol/root rd.lvm.lv=ol/swap rhgb quiet  
numa=off transparent_hugepage=never clocksource=tsc"
```

5. Run the following command to update `GRUB` and ensure that these settings are retained even after a reboot:

```
# grub2-mkconfig -o /boot/grub2/grub.cfg
```

Installing the cvuqdisk RPM for Linux

If you do not use an Oracle Database Preinstallation RPM, and you want to use the Configuration Verification Utility, then you must install the `cvuqdisk` RPM.

Without `cvuqdisk`, Configuration Verification Utility (CVU) cannot discover shared disks, and you receive the error message "Package `cvuqdisk` not installed" when you run Configuration Verification Utility. Use the `cvuqdisk` RPM for your hardware (for example, `x86_64`).

1. Locate the `cvuqdisk` RPM package, which is located in the directory `Grid_home/cv/rpm`. Where `Grid_home` is the Oracle Grid Infrastructure home directory.
2. Copy the `cvuqdisk` package to each node on the cluster. You should ensure that each node is running the same version of Linux.
3. Log in as `root`.
4. Use the following command to find if you have an existing version of the `cvuqdisk` package:

```
# rpm -qi cvuqdisk
```

If you have an existing version of `cvuqdisk`, then enter the following command to deinstall the existing version:

```
# rpm -e cvuqdisk
```

5. Set the environment variable `CVUQDISK_GRP` to point to the group that owns `cvuqdisk`, typically `oinstall`. For example:

```
# CVUQDISK_GRP=oinstall; export CVUQDISK_GRP
```

6. In the directory where you have saved the `cvuqdisk` RPM, use the command `rpm -iv package` to install the `cvuqdisk` package. For example:

```
# rpm -iv cvuqdisk-1.0.10-1.rpm
```

Reviewing HugePages Memory Allocation

Review this information if your operating system has HugePages enabled.

On Linux platform installations, Oracle recommends that you use HugePages to obtain the best performance for Oracle Databases. When you upgrade Oracle Grid Infrastructure and Oracle Databases on servers that have HugePages enabled, Oracle recommends that you review your HugePages memory allocation requirements.

Setting Transparent HugePages to `madvise`

Transparent HugePages memory is enabled by default with Oracle Linux. However, for optimal performance, Oracle recommends that you set Transparent HugePages to `madvise` on all

Oracle Database servers UEK7 and later kernels and not disable Transparent HugePages as was recommended in prior releases.

If you install Oracle Database Preinstallation RPM, then it sets Transparent HugePages to `madvise` on all Oracle Database servers UEK7 and later kernels.

To set `madvise` on Transparent HugePages:

1. For Oracle Linux and Red Hat Enterprise Linux, add or modify the `transparent_hugepage=madvise` parameter in the `/etc/default/grub` file:

```
GRUB_TIMEOUT=5
GRUB_DISTRIBUTOR="$(sed 's, release .*$,,g' /etc/system-release)"
GRUB_DEFAULT=saved
GRUB_DISABLE_SUBMENU=true
GRUB_TERMINAL_OUTPUT="console"
GRUB_CMDLINE_LINUX="crashkernel=auto rhgb quiet numa=off
transparent_hugepage=madvise"
GRUB_DISABLE_RECOVERY="true"
```

 **Note:**

The file name may vary depending on your operating system and hardware. For example, on Oracle Cloud Infrastructure (OCI) the `grub.cfg` file is located at `/boot/efi/EFI/redhat/`. Check your operating system documentation for the exact file name.

2. Run the `grub2-mkconfig` command to regenerate the `grub.cfg` file.

On Oracle Linux 8

```
# grub2-mkconfig -o /boot/grub2/grub.cfg
```

On Oracle Linux 9

```
grub2-mkconfig -o /boot/grub2/grub.cfg --update-bls-cmdline
```

3. Restart the system to make the changes permanent. If you do not want to restart your system, then enter the following command:

```
# echo madvise >
  /sys/kernel/mm/transparent_hugepage/enabled
```

4. To check if Transparent HugePages is enabled and configured with `madvise`, run one of the following commands as the `root` user:

Oracle Linux kernels:

```
# cat /sys/kernel/mm/transparent_hugepage/enabled
```

Red Hat Enterprise Linux kernels:

```
# cat /sys/kernel/mm/redhat_transparent_hugepage/enabled
```

The following is a sample output that shows Transparent HugePages is being used and set to `madvise`.

```
always [madvise] never
```

Enabling the Name Service Cache Daemon

To allow Oracle Clusterware to better tolerate network failures with NAS devices or NFS mounts, enable the Name Service Cache Daemon (`nscd`).

To check to see if `nscd` is set to load when the system is restarted, enter the command `chkconfig --list nscd`. For example:

```
# chkconfig --list nscd
nscd                0:off 1:off 2:off 3:on  4:off 5:off 6:off
```

`nscd` is turned on for run level 3, and turned off for run level 5. The `nscd` should be turned on for both run level 3 and run level 5.

To change the configuration to ensure that `nscd` is on for both run level 3 and run level 5, enter the following command as `root`:

```
# chkconfig --level 35 nscd on
```

To start up `nscd` in the current session, enter the command as `root`:

```
# service nscd start
```

To restart `nscd` with the new setting, enter the following command as `root`:

```
# service nscd restart
```

```
nscd
```

```
systemctl --all |grep nscd
nscd.service loaded active running Name Service Cache Daemon
```

Verifying the Disk I/O Scheduler on Linux 8 and Later Systems

Disk I/O schedulers reorder, delay, or merge requests for disk I/O to achieve better throughput and lower latency.

Linux has multiple disk I/O schedulers available, including `mq-deadline`, `none`, `kyber`, and `bfq` on Oracle Linux 8 and later, RHEL 8 and later, and SUSE Linux Enterprise Server 15 and later systems. You should consult with your storage vendor for the appropriate I/O scheduler configuration to achieve best performance on Oracle Automatic Storage Management (Oracle ASM).

In general, Oracle recommends that you set the I/O Scheduler to `mq-deadline` for rotating storage devices (HDDs) and to `none` for non-rotating storage devices such as SSDs and NVMe

on Oracle Linux 8 and later, RHEL 8 and later, and SUSE Linux Enterprise Server 15 and later systems.

On all cluster nodes, enter the following command as `root` to verify the configured disk I/O scheduler value.

```
cat /sys/block/${ASM_DISK}/queue/scheduler  
none [mq-deadline] kyber bfq
```

In this example, the default disk I/O scheduler is `mq-deadline` and `ASM_DISK` is a rotational Oracle ASM disk device.

 **Note:**

Contact your storage vendor for more information about how to configure I/O scheduler on Linux for your storage devices.

Using Automatic SSH Configuration During Installation

To install Oracle software, configure secure shell (SSH) connectivity between all cluster member nodes.

Oracle Universal Installer (OUI) uses the `ssh` and `sftp` commands during installation to run remote commands on and copy files to the other cluster nodes. You must configure SSH so that these commands do not prompt for a password.

 **Note:**

Oracle configuration assistants use SSH for configuration operations from local to remote nodes. Oracle Enterprise Manager also uses SSH. RSH is no longer supported.

You can configure SSH from the OUI interface during installation for the user account running the installation. The automatic configuration creates passwordless SSH connectivity between all cluster member nodes. Oracle recommends that you use the automatic procedure if possible.

To enable the script to run, you must remove `stty` commands from the profiles of any existing Oracle software installation owners you want to use, and remove other security measures that are triggered during a login, and that generate messages to the terminal. These messages, mail checks, and other displays prevent Oracle software installation owners from using the SSH configuration script that is built into OUI. If they are not disabled, then SSH must be configured manually before an installation can be run.

In rare cases, Oracle Clusterware installation can fail during the "AttachHome" operation when the remote node closes the SSH connection. To avoid this problem, set the timeout wait to unlimited by setting the following parameter in the SSH daemon configuration file `/etc/ssh/sshd_config` on all cluster nodes:

```
LoginGraceTime 0
```


Setting Network Time Protocol for Cluster Time Synchronization

You can use operating system configured network time protocol (NTP) such as `chronyd` or `ntpd` for time synchronization.

 **Note:**

Cluster Time Synchronization Service (CTSS) is desupported in Oracle Database 23ai.

To synchronize time between cluster member nodes, use either an operating system configured network time protocol such as `ntp` or `chrony`. To verify that you have network time synchronization configured, you can use the `cluvfy comp clocksync -n allnodes` command.

Oracle Clusterware requires the same time zone environment variable setting on all cluster nodes. During installation, the installation process picks up the time zone (TZ) environment variable setting of the Grid installation owner on the node where Oracle Universal Installer (OUI) runs, and uses that time zone value on all nodes as the default TZ environment variable setting for all processes managed by Oracle Clusterware. The time zone default is used for databases, Oracle ASM, and any other managed processes. You can ensure time synchronization using an operating system configured network time protocol (NTP) such as `chronyd` or `ntpd`.

 **Note:**

Before starting the installation of Oracle Grid Infrastructure, Oracle recommends that you ensure the clocks on all nodes are set to the same time.

Deactivating the NTP Service

To deactivate the Network Time Protocol (NTP) service, you must stop the `ntpd` and `chronyd` services, and disable them from the initialization sequences.

Complete these steps on Oracle Linux 8 and Red Hat Enterprise Linux 8:

1. Run the following commands as the `root` user to stop the `ntpd` service:

```
# systemctl stop ntpd
# systemctl disable ntpd
```

2. Rename the NTP-related configuration files in the `/etc` directory.

3. Run the following commands as the `root` user to stop the `chronyd` service:

```
# systemctl stop chronyd
# systemctl disable chronyd
```

4. Remove the `chronyd` service configuration file.

Verifying Digital Signature and Integrity of Installation Archive Files

Starting with Oracle Database 23ai, Oracle digitally signs the installation archive files with Oracle certificates to ensure the integrity of the packages before you deploy them in your environments.

Use the Java utility `jarsigner` to verify the integrity of your Oracle Database, Oracle Database Client, Oracle Grid Infrastructure, Oracle Examples, Oracle Gateways, or Oracle GSM installation archive files. You can verify the integrity of the installation archive files before you extract the installation files.

Quick Verification

To quickly verify the installation archive files, use the `jarsigner` command with the `-verify` option:

1. Go to the directory where you have downloaded the installation archive files.
2. Run this command to check your installation archive file:

```
jarsigner -verify installation_archive_file
```

For example, to check the Oracle Database gold image:

```
jarsigner -verify db_home.zip
```

```
jar verified.
```

Detailed Certificate Information

If you want detailed certificate information, then use the `-verbose:summary` and `-certs` along with the `-verify` option.

1. Go to the directory where you have downloaded the installation archive files.
2. Run this command to check your installation archive file:

```
jarsigner -verify -verbose:summary -certs installation_archive_file
```

For example, to check the Oracle Database gold image:

```
jarsigner -verify -verbose:summary -certs db_home.zip
```

The output is similar to the following:

```
2237119 Fri Feb 17 07:02:30 UTC 2023 META-INF/MANIFEST.MF
```

```
>>> Signer
      X.509, CN="Oracle America, Inc.", O="Oracle America, Inc.",
      L=Redwood City, ST=California, C=US
      [
```

```

Signature algorithm: SHA256withRSA, 3072-bit key
[certificate is valid from 8/19/21 12:00 AM to 8/19/23 11:59 PM]
X.509, CN=DigiCert Trusted G4 Code Signing RSA4096 SHA384 2021 CA1,
O="DigiCert, Inc.", C=US
[
Signature algorithm: SHA384withRSA, 4096-bit key
[certificate is valid from 4/29/21 12:00 AM to 4/28/36 11:59 PM]
X.509, CN=DigiCert Trusted Root G4, O=DigiCert Inc, C=US
[
Signature algorithm: SHA384withRSA, 4096-bit key
[trusted certificate]
>>> TSA
X.509, CN=DigiCert Timestamp 2022 - 2, O=DigiCert, C=US
[
Signature algorithm: SHA256withRSA, 4096-bit key
[certificate is valid from 9/21/22 12:00 AM to 11/21/33 11:59 PM]
X.509, CN=DigiCert Trusted G4 RSA4096 SHA256 TimeStamping CA,
O="DigiCert, Inc.", C=US
[
Signature algorithm: SHA256withRSA, 4096-bit key
[certificate is valid from 3/23/22 12:00 AM to 3/22/37 11:59 PM]
X.509, CN=DigiCert Trusted Root G4, O=DigiCert Inc, C=US
[
Signature algorithm: SHA384withRSA, 4096-bit key
[certificate is valid from 8/1/22 12:00 AM to 11/9/31 11:59 PM]

2237281 Fri Feb 17 07:02:32 UTC 2023 META-INF/ORACLE_C.SF (and 1
more)

(Signature related entries)

0 Fri Feb 17 05:41:24 UTC 2023 OPatch/ (and 1897 more)

(Directory entries)

2977 Tue Dec 20 08:02:16 UTC 2022 OPatch/README.txt (and 20199 more)

[entry was signed on 2/17/23 7:02 AM]
>>> Signer
X.509, CN="Oracle America, Inc.", O="Oracle America, Inc.",
L=Redwood City, ST=California, C=US
[
Signature algorithm: SHA256withRSA, 3072-bit key
[certificate is valid from 8/19/21 12:00 AM to 8/19/23 11:59 PM]
X.509, CN=DigiCert Trusted G4 Code Signing RSA4096 SHA384 2021 CA1,
O="DigiCert, Inc.", C=US
[
Signature algorithm: SHA384withRSA, 4096-bit key
[certificate is valid from 4/29/21 12:00 AM to 4/28/36 11:59 PM]
X.509, CN=DigiCert Trusted Root G4, O=DigiCert Inc, C=US
[
Signature algorithm: SHA384withRSA, 4096-bit key
[trusted certificate]
>>> TSA
X.509, CN=DigiCert Timestamp 2022 - 2, O=DigiCert, C=US
[

```

```
Signature algorithm: SHA256withRSA, 4096-bit key
[certificate is valid from 9/21/22 12:00 AM to 11/21/33 11:59 PM]
X.509, CN=DigiCert Trusted G4 RSA4096 SHA256 TimeStamping CA,
O="DigiCert, Inc.", C=US
[
Signature algorithm: SHA256withRSA, 4096-bit key
[certificate is valid from 3/23/22 12:00 AM to 3/22/37 11:59 PM]
X.509, CN=DigiCert Trusted Root G4, O=DigiCert Inc, C=US
[
Signature algorithm: SHA384withRSA, 4096-bit key
[certificate is valid from 8/1/22 12:00 AM to 11/9/31 11:59 PM]
```

```
s = signature was verified
m = entry is listed in manifest
k = at least one certificate was found in keystore
i = at least one certificate was found in identity scope
```

```
- Signed by "CN="Oracle America, Inc.", O="Oracle America, Inc.",
L=Redwood City, ST=California, C=US"
Digest algorithm: SHA-256
Signature algorithm: SHA256withRSA, 3072-bit key
Timestamped by "CN=DigiCert Timestamp 2022 - 2, O=DigiCert, C=US" on Fri
Feb 17 07:02:33 UTC 2023
Timestamp digest algorithm: SHA-256
Timestamp signature algorithm: SHA256withRSA, 4096-bit key
```

jar verified.

```
The signer certificate will expire on 2023-08-19.
The timestamp will expire on 2031-11-09.
```

For more jarsigner options, type `jarsigner -h` or review the jarsigner documentation:

[jarsigner Reference](#)

5

Configuring Networks for Oracle Grid Infrastructure and Oracle RAC

Check that you have the networking hardware and internet protocol (IP) addresses required for an Oracle Grid Infrastructure for a cluster installation.

Note:

If you have a firewall running, ensure that all the required ports are open. See, *Port Numbers and Protocols of Oracle Components* for a list of port numbers and protocols configured for Oracle Database components.

- [About Oracle Grid Infrastructure Network Configuration Options](#)
Ensure that you have the networking hardware and internet protocol (IP) addresses required for an Oracle Grid Infrastructure for a cluster installation.
- [Understanding Network Addresses](#)
During installation, you are asked to identify the planned use for each network interface that Oracle Universal Installer (OUI) detects on your cluster node.
- [Network Interface Hardware Minimum Requirements](#)
Review these requirements to ensure that you have the minimum network hardware technology for Oracle Grid Infrastructure clusters.
- [Private IP Interface Configuration Requirements](#)
Requirements for private interfaces depend on whether you are using single or multiple Interfaces.
- [IPv4 and IPv6 Protocol Requirements](#)
Oracle Grid Infrastructure and Oracle RAC support the standard IPv6 address notations specified by RFC 2732 and global and site-local IPv6 addresses as defined by RFC 4193.
- [Oracle Grid Infrastructure IP Name and Address Requirements](#)
Review this information for Oracle Grid Infrastructure IP Name and Address requirements.
- [Broadcast Requirements for Networks Used by Oracle Grid Infrastructure](#)
Broadcast communications (ARP and UDP) must work properly across all the public and private interfaces configured for use by Oracle Grid Infrastructure.
- [Multicast Requirements for Networks Used by Oracle Grid Infrastructure](#)
For each cluster member node, the Oracle mDNS daemon uses multicasting on all interfaces to communicate with other nodes in the cluster.
- [Domain Delegation to Grid Naming Service](#)
If you are configuring Grid Naming Service (GNS) for a standard cluster, then before installing Oracle Grid Infrastructure you must configure DNS to send to GNS any name resolution requests for the subdomain served by GNS.
- [Configuration Requirements for Oracle Flex Clusters](#)
Understand Oracle Flex Clusters and their configuration requirements.

- [Grid Naming Service Cluster Configuration Example](#)
Review this example to understand Grid Naming Service configuration.
- [Manual IP Address Configuration Example](#)
If you choose not to use GNS, then before installation you must configure public, virtual, and private IP addresses.
- [Network Interface Configuration Options](#)
During installation, you are asked to identify the planned use for each network adapter (or network interface) that Oracle Universal Installer (OUI) detects on your cluster node.
- [Multiple Private Interconnects and Oracle Linux](#)
Review this information for settings for the `rp_filter` parameter for Oracle RAC systems that use multiple NICs for the private interconnect.
- [Creating SCAN Client Data File](#)
Generate a SCAN client data file and copy the file to the SCAN client cluster member node on which you are installing Oracle Grid Infrastructure.

About Oracle Grid Infrastructure Network Configuration Options

Ensure that you have the networking hardware and internet protocol (IP) addresses required for an Oracle Grid Infrastructure for a cluster installation.

Oracle Clusterware Networks

An Oracle Clusterware configuration requires at least two interfaces:

- A public network interface, on which users and application servers connect to access data on the database server.
- A private network interface for internode communication.

You can configure a network interface to use either the IPv4 protocol, or the IPv6 protocol on a given network. If you use redundant network interfaces (bonded or teamed interfaces), then be aware that Oracle does not support configuring one interface to support IPv4 addresses and the other to support IPv6 addresses. You must configure network interfaces of a redundant interface pair with the same IP protocol.

All the nodes in the cluster must use the same IP protocol configuration. Either all the nodes use only IPv4, or all the nodes use only IPv6. You cannot have some nodes in the cluster configured to support only IPv6 addresses, and other nodes in the cluster configured to support only IPv4 addresses.

The VIP agent supports the generation of IPv6 addresses using the Stateless Address Autoconfiguration Protocol (RFC 2462), and advertises these addresses with GNS. Run the `srvctl config network` command to determine if Dynamic Host Configuration Protocol (DHCP) or stateless address autoconfiguration is being used.

Note:

The Highly Available Grid Naming Service feature of Grid Naming Service (GNS) in Oracle Grid Infrastructure is deprecated in Oracle Database 23ai.

See the Certify page on My Oracle Support for the most up-to-date information about supported network protocols and hardware for Oracle RAC:

<https://support.oracle.com>

Understanding Network Addresses

During installation, you are asked to identify the planned use for each network interface that Oracle Universal Installer (OUI) detects on your cluster node.

Identify each interface as a public or private interface, or as an interface that you do not want Oracle Grid Infrastructure or Oracle ASM to use. Public and virtual internet protocol (VIP) addresses are configured on public interfaces. Private addresses are configured on private interfaces.

- [About the Public IP Address](#)
The public IP address is assigned dynamically using Dynamic Host Configuration Protocol (DHCP), or defined statically in a Domain Name System (DNS) or in a hosts file.
- [About the Private IP Address](#)
Oracle Clusterware uses interfaces marked as private for internode communication.
- [About the Virtual IP Address](#)
The virtual IP (VIP) address is registered in the grid naming service (GNS), the DNS, or in a hosts file.
- [About the Grid Naming Service \(GNS\) Virtual IP Address](#)
The GNS virtual IP address is a static IP address configured in the Domain Name System (DNS).
- [About the SCAN](#)
Oracle Database clients connect to the database using a Single Client Access Name (SCAN). The SCAN is optional for most deployments.
- [About Shared SCAN](#)
Shared SCAN provides the capability to share SCAN VIPs across multiple clusters, thus reducing the number of IP addresses that must be assigned when deploying Oracle Clusters.

About the Public IP Address

The public IP address is assigned dynamically using Dynamic Host Configuration Protocol (DHCP), or defined statically in a Domain Name System (DNS) or in a hosts file.

The public IP address uses the public interface (the interface with access available to clients). The public IP address is the primary address for a cluster member node, and should be the address that resolves to the name returned when you enter the command `hostname`.

If you configure IP addresses manually, then avoid changing host names after you complete the Oracle Grid Infrastructure installation, including adding or deleting domain qualifications. A node with a new host name is considered a new host, and must be added to the cluster. A node under the old name appears to be down until it is removed from the cluster.

About the Private IP Address

Oracle Clusterware uses interfaces marked as private for internode communication.

Each cluster node must have an interface that you identify during installation as a private interface. Private interfaces must have addresses configured for the interface itself, but no additional configuration is required. Oracle Clusterware uses the interfaces you identify as private for the cluster interconnect. If you identify multiple interfaces during information for the private network, then Oracle Clusterware configures them with Redundant Interconnect Usage.

Any interface that you identify as private must be on a subnet that connects to every node of the cluster. Oracle Clusterware uses all the interfaces you identify for use as private interfaces.

For the private interconnects, because of Cache Fusion and other traffic between nodes, Oracle strongly recommends using a physically separate, private network. If you configure addresses using a DNS, then you should ensure that the private IP addresses are reachable only by the cluster nodes.

You can choose multiple interconnects either during installation or postinstallation using the `oifcfg setif` command.

After installation, if you modify the interconnect for Oracle Real Application Clusters (Oracle RAC) with the `CLUSTER_INTERCONNECTS` initialization parameter, then you must change the interconnect to a private IP address, on a subnet that is not used with a public IP address, nor marked as a public subnet by `oifcfg`. Oracle does not support changing the interconnect to an interface using a subnet that you have designated as a public subnet.

You should not use a firewall on the network with the private network IP addresses, because this can block interconnect traffic.

About the Virtual IP Address

The virtual IP (VIP) address is registered in the grid naming service (GNS), the DNS, or in a hosts file.

Note:

The Highly Available Grid Naming Service feature of Grid Naming Service (GNS) in Oracle Grid Infrastructure is deprecated in Oracle Database 23ai.

Note:

Starting with Oracle Grid Infrastructure 18c, using VIP is optional for Oracle Clusterware deployments. You can specify VIPs for all or none of the cluster nodes. However, specifying VIPs for selected cluster nodes is not supported.

Select an address for your VIP that meets the following requirements:

- The IP address and host name are currently unused (it can be registered in a DNS, but should not be accessible by a ping command)
- The VIP is on the same subnet as your public interface

If you are not using Grid Naming Service (GNS), then determine a virtual host name for each node. A virtual host name is a public node name that reroutes client requests sent to the node if the node is down. Oracle Database uses VIPs for client-to-database connections, so the VIP address must be publicly accessible. Oracle recommends that you provide a name in the format `hostname-vip`. For example: `myclstr2-vip`.

About the Grid Naming Service (GNS) Virtual IP Address

The GNS virtual IP address is a static IP address configured in the Domain Name System (DNS).

 **Note:**

The Highly Available Grid Naming Service feature of Grid Naming Service (GNS) in Oracle Grid Infrastructure is deprecated in Oracle Database 23ai. The highly-available GNS provides the ability to run multiple GNS instances in a multi-cluster environment with different roles. This feature is being deprecated. There is no replacement.

The DNS delegates queries to the GNS virtual IP address, and the GNS daemon responds to incoming name resolution requests at that address. Within the subdomain, the GNS enables the cluster to map host names and IP addresses dynamically as nodes are added and removed from the cluster, without requiring additional host configuration in the DNS.

To enable GNS, you must have your network administrator provide a set of IP addresses for a subdomain assigned to the cluster (for example, `grid.example.com`), and delegate DNS requests for that subdomain to the GNS virtual IP address for the cluster, which GNS serves. DHCP provides the set of IP addresses to the cluster. DHCP must be available on the public network for the cluster.

Related Topics

- *Oracle Clusterware Administration and Deployment Guide*

About the SCAN

Oracle Database clients connect to the database using a Single Client Access Name (SCAN). The SCAN is optional for most deployments.

The SCAN and its associated IP addresses provide a stable name for clients to use for connections, independent of the nodes that make up the cluster. SCAN addresses, virtual IP addresses, and public IP addresses must all be on the same subnet.

The SCAN is a virtual IP name, similar to the names used for virtual IP addresses, such as `node1-vip`. However, unlike a virtual IP, the SCAN is associated with the entire cluster, rather than an individual node, and associated with multiple IP addresses, not only one address.

The SCAN resolves to multiple IP addresses reflecting multiple listeners in the cluster that handle public client connections. When a client submits a request, the SCAN listener listening on a SCAN IP address and the SCAN port is made available to a client. Because all services on the cluster are registered with the SCAN listener, the SCAN listener replies with the address of the local listener on the least-loaded node where the service is currently being offered. Finally, the client establishes connection to the service through the listener on the node where service is offered. All of these actions take place transparently to the client without any explicit configuration required in the client.

During installation, listeners are created. These SCAN listeners listen on the SCAN IP addresses. The SCAN listeners are started on nodes determined by Oracle Clusterware. Oracle Net Services routes application requests to the least-loaded instance providing the service. Because the SCAN addresses resolve to the cluster, rather than to a node address in the cluster, nodes can be added to or removed from the cluster without affecting the SCAN address configuration. The SCAN listener also supports HTTP protocol for communication with Oracle XML Database (XDB).

The SCAN should be configured so that it is resolvable either by using Grid Naming Service (GNS) within the cluster, or by using Domain Name Service (DNS) resolution. For high availability and scalability, Oracle recommends that you configure the SCAN name so that it

resolves to three IP addresses. Ensure that the SCAN resolves to at least one IP address. However, configuring less than the recommended three IP addresses may impact the availability to connect to the cluster.

If you specify a GNS domain, then the SCAN name defaults to `clustername-scan.cluster_name.GNS_domain`. Otherwise, it defaults to `clustername-scan.current_domain`. For example, if you start Oracle Grid Infrastructure installation from the server `node1`, the cluster name is `mycluster`, and the GNS domain is `grid.example.com`, then the SCAN Name is `mycluster-scan.mycluster.grid.example.com`.

The database registers with the SCAN listener through the remote listener parameter in the `init.ora` file. The `REMOTE_LISTENER` parameter must be set to `SCAN:PORT`. Do not set it to a `TNSNAMES` alias with a single address for the SCAN, for example, using `HOST= SCAN_name`.

Provide SCAN addresses for client access to the cluster. These addresses must be configured as round robin addresses on the domain name service (DNS), if DNS is used. Oracle recommends that you supply three SCAN addresses.

Identify public and private interfaces. Oracle Universal Installer configures public interfaces for use by public and virtual IP addresses, and configures private IP addresses on private interfaces. The private subnet that the private interfaces use must connect all the nodes you intend to have as cluster members. The SCAN must be in the same subnet as the public interface.

Related Topics

- *Oracle Real Application Clusters Administration and Deployment Guide*

About Shared SCAN

Shared SCAN provides the capability to share SCAN VIPs across multiple clusters, thus reducing the number of IP addresses that must be assigned when deploying Oracle Clusters.

In earlier versions of the Oracle Clusterware, SCAN VIPs were configured on a per cluster basis. With shared SCAN, the same SCAN is used among multiple clusters, so that only one of these clusters runs SCAN listeners. The databases of all clusters use the SCAN VIPs of this cluster, for all their database connections. Each cluster has its own set of ports, instead of SCAN VIPs. Clusters using shared SCAN can name their database services as desired, without naming conflicts if one or more of these clusters are configured with services of the same name.

Network Interface Hardware Minimum Requirements

Review these requirements to ensure that you have the minimum network hardware technology for Oracle Grid Infrastructure clusters.

Public Network for Each Node

Public networks provide access to clients for database services. Public networks must meet these minimum requirements:

- **Adapters:** Each node must have at least one public network adapter or network interface cards (NIC).

Oracle supports the use of link aggregations, bonded, trunked or teamed networks for improved bandwidth and high availability.

 **Note:**

Refer to the My Oracle Support Note 2646289.1 for a list of supported bonding modes.

- Protocol: Each public interface must support TCP/IP.

Private Network for Each Node

Private networks (also called interconnects) are networks that only cluster member nodes can access. They use switches for connections. Private networks must meet these minimum requirements:

- Adapters: Each node must have at least one private network adapter or network interface cards (NIC).

Oracle recommends that you configure interconnects using Redundant Interconnect Usage, in which multiple network adapters are configured with addresses in the link-local range to provide highly available IP (HAIP) addresses for the interconnect. You can configure Redundant Interconnect Usage either during installation, or after installation by using Oracle Interface Configuration Tool (OIFCFG), to provide improved bandwidth and high availability.

Oracle also supports the use of link aggregations, bonded, trunked or teamed networks for improved bandwidth and high availability.

- Protocol: User datagram protocol (UDP) using high-speed network adapters and switches that support TCP/IP, or Reliable Datagram Sockets (RDS) with Infiniband.

Switches: You must use switches for interconnects that support TCP/IP. Oracle recommends that you use dedicated switches. The minimum switch speed is 1 Gigabit Ethernet.

Oracle recommends that you configure Jumbo Frames with an MTU size of 9000 (MTU=9000) on your private network.

 **Note:**

When configuring Jumbo Frames, ensure that all the components of the private network including host adapters, network drivers, and switches support using Jumbo Frames.

Local Area Network Technology

Oracle does not support token-rings or crossover cables for the interconnect. Oracle supports Jumbo Frames and Infiniband. When you use Infiniband on the interconnect, Oracle supports using the RDS protocol.

If you have a shared Ethernet VLAN deployment, with shared physical adapter, ensure that you apply standard Ethernet design, deployment, and monitoring best practices to protect against cluster outages and performance degradation due to common shared Ethernet switch network events.

Storage Networks

Oracle Automatic Storage Management and Oracle Real Application Clusters require network-attached storage.

Oracle Automatic Storage Management (Oracle ASM): The network interfaces used for Oracle Clusterware files are also used for Oracle ASM.

Third-party storage: Oracle recommends that you configure additional interfaces for storage.

Related Topics

- [My Oracle Support Note 2646289.1](#)

Private IP Interface Configuration Requirements

Requirements for private interfaces depend on whether you are using single or multiple interfaces.

Network Requirements for Single Interface Private Network Clusters

- Each node's private interface for interconnects must be on the same subnet.
- The subnet must connect to every node of the cluster.

For example, if the private interfaces have a subnet mask of 255.255.255.0, then your private network is in the range 192.168.0.0--192.168.0.255, and your private addresses must be in the range of 192.168.0.[0-255]. If the private interfaces have a subnet mask of 255.255.0.0, then your private addresses can be in the range of 192.168.[0-255].[0-255]

- Both IPv4 and IPv6 addresses are supported.

Network Requirements for Redundant Interconnect Usage Clusters

With Redundant Interconnect Usage, you can identify multiple interfaces to use for the cluster private network, without the need of using bonding or other technologies.

When you define multiple interfaces, Oracle Clusterware creates from one to four highly available IP (HAIP) addresses. Oracle RAC and Oracle Automatic Storage Management (Oracle ASM) instances use these interface addresses to ensure highly available, load-balanced interface communication between nodes. The installer enables Redundant Interconnect Usage to provide a high availability private network. By default, Oracle Grid Infrastructure software uses all of the HAIP addresses for private network communication, providing load-balancing across the set of interfaces you identify for the private network. If a private interconnect interface fails or become non-communicative, then Oracle Clusterware transparently moves the corresponding HAIP address to one of the remaining functional interfaces.

- Each private interface should be on a different subnet.
- Each cluster member node must have an interface on each private interconnect subnet, and these subnets must connect to every node of the cluster.

For example, you can have private networks on subnets 192.168.0 and 10.0.0, but each cluster member node must have an interface connected to the 192.168.0 and 10.0.0 subnets.

- Endpoints of all designated interconnect interfaces must be completely reachable on the network. There should be no node that is not connected to every private network interface.

You can test if an interconnect interface is reachable using `ping`.

- You can use IPv4 and IPv6 addresses for the interfaces with Oracle Clusterware Redundant interconnects.

 **Note:**

During installation, you can define up to four interfaces for the private network. The number of HAIP addresses created during installation is based on both physical and logical interfaces configured for the network adapter. After installation, you can define additional interfaces. If you define more than four interfaces as private network interfaces, then be aware that Oracle Clusterware activates only four of the interfaces at a time. However, if one of the four active interfaces fails, then Oracle Clusterware transitions the HAIP addresses configured to the failed interface to one of the reserve interfaces in the defined set of private interfaces.

Related Topics

- *Oracle Clusterware Administration and Deployment Guide*

IPv4 and IPv6 Protocol Requirements

Oracle Grid Infrastructure and Oracle RAC support the standard IPv6 address notations specified by RFC 2732 and global and site-local IPv6 addresses as defined by RFC 4193.

Configuring Public VIPs

Cluster member node interfaces can be configured to use IPv4, IPv6, or both types of Internet protocol addresses. During installation, you can configure VIPs for a given public network as IPv4 or IPv6 types of addresses. You can configure an IPv6 cluster by selecting VIP and SCAN names that resolve to addresses in an IPv6 subnet for the cluster, and selecting that subnet as public during installation. After installation, you can also configure cluster member nodes with a mixture of IPv4 and IPv6 addresses.

If you install using static virtual IP (VIP) addresses in an IPv4 cluster, then the VIP names you supply during installation should resolve only to IPv4 addresses. If you install using static IPv6 addresses, then the VIP names you supply during installation should resolve only to IPv6 addresses.

During installation, you cannot configure the cluster with VIP and SCAN names that resolve to both IPv4 and IPv6 addresses. You cannot configure VIPs and SCANS on some cluster member nodes to resolve to IPv4 addresses, and VIPs and SCANS on other cluster member nodes to resolve to IPv6 addresses. Oracle does not support this configuration.

Configuring Private IP Interfaces (Interconnects)

You can configure the private network either as an IPv4 network or IPv6 network.

Redundant Network Interfaces

If you configure redundant network interfaces for a public or VIP node name, then configure both interfaces of a redundant pair to the same address protocol. Also ensure that private IP interfaces use the same IP protocol. Oracle does not support names using redundant interface configurations with mixed IP protocols. You must configure both network interfaces of a redundant pair with the same IP protocol.

GNS

Oracle Grid Infrastructure supports IPv4 DHCP addresses, and IPv6 addresses configured with the Stateless Address Autoconfiguration protocol, as described in RFC 2462.



Note:

Link-local and site-local IPv6 addresses as defined in RFC 1884 are not supported.

Oracle Grid Infrastructure IP Name and Address Requirements

Review this information for Oracle Grid Infrastructure IP Name and Address requirements.

For small clusters, you can use a static configuration of IP addresses. For large clusters, manually maintaining the large number of required IP addresses becomes too cumbersome. Use Oracle Grid Naming Service with large clusters to ease network administration costs.

- [About Oracle Grid Infrastructure Name Resolution Options](#)
Before starting the installation, you must have at least two interfaces configured on each node: One for the private IP address, and one for the public IP address.
- [Cluster Name and SCAN Requirements](#)
Review this information before you select the cluster name and SCAN.
- [IP Name and Address Requirements For Grid Naming Service \(GNS\)](#)
Review this information for IP name and address requirements for Grid Naming Service (GNS).
- [IP Name and Address Requirements for Manual Configuration of Cluster](#)
For Oracle Flex Clusters, configure static cluster node names and addresses if you do not enable GNS.
- [Confirming the DNS Configuration for SCAN](#)
Use the `nslookup` command to confirm that the DNS is correctly associating the SCAN with the addresses.

About Oracle Grid Infrastructure Name Resolution Options

Before starting the installation, you must have at least two interfaces configured on each node: One for the private IP address, and one for the public IP address.

During installation, you are asked to identify the planned use for each network interface that Oracle Universal Installer (OUI) detects on your cluster node. Identify each interface as a public or private interface, or as an interface that you do not want Oracle Grid Infrastructure or Oracle ASM to use. Public and virtual internet protocol (VIP) addresses are configured on public interfaces. Private addresses are configured on private interfaces.



Note:

All name servers in the DNS configuration for a cluster must resolve to all host names used in the cluster, such as cluster node host name, VIP host name, and SCAN host name.

Configure IP addresses with one of the following options:

Dynamic IP address assignment using Oracle Grid Naming Service (GNS)

If you select this option, then network administrators delegate a subdomain that GNS resolves. GNS requirements are different depending on how you configure zone delegation. If you

configure GNS with zone delegation, then GNS is delegated a domain for which it resolves service requests. If you configure GNS without zone delegation, then GNS has a virtual IP address that is resolved by a DNS.

 **Note:**

The Highly Available Grid Naming Service feature of Grid Naming Service (GNS) in Oracle Grid Infrastructure is deprecated in Oracle Database 23ai.

For GNS with zone delegation:

- For IPv4, a DHCP service running on the public network the cluster uses
- For IPv6, an autoconfiguration service running on the public network the cluster uses
- Enough addresses on the DHCP server to provide one IP address for each node, and three IP addresses for the cluster used by the Single Client Access Name (SCAN) for the cluster

Static IP address assignment using DNS or host file resolution

If you select this option, then network administrators assign a fixed IP address for each physical host name in the cluster, and for IPs for VIPs managed by Oracle Clusterware. In addition, either domain name server (DNS) based static name resolution is used for each node, or host files for both the clusters and clients have to be updated, resulting in limited SCAN functionality. Selecting this option requires that you request network administration updates when you modify the cluster.

For GNS without zone delegation, configure a GNS virtual IP address (VIP) for the cluster. To enable Oracle Flex Cluster, you must at least configure a GNS virtual IP address.

Cluster Name and SCAN Requirements

Review this information before you select the cluster name and SCAN.

Cluster Name and SCAN Requirements

Cluster Name must meet the following requirements:

- The cluster name is case-insensitive, must be unique across your enterprise, must be at least one character long and no more than 15 characters in length, must be alphanumeric and may contain hyphens (-). Underscore characters () are not allowed.
- The SCAN and cluster name are entered in separate fields during installation, so cluster name requirements do not apply to the name used for the SCAN, and the SCAN can be longer than 15 characters. If you enter a domain with the SCAN name, and you want to use GNS with zone delegation, then the domain must be the GNS domain.

 **Note:**

Select your cluster name carefully. After installation, you can only change the cluster name by reinstalling Oracle Grid Infrastructure.

IP Name and Address Requirements For Grid Naming Service (GNS)

Review this information for IP name and address requirements for Grid Naming Service (GNS).

Note:

The Highly Available Grid Naming Service feature of Grid Naming Service (GNS) in Oracle Grid Infrastructure is deprecated in Oracle Database 23ai.

IP Name and Address Requirements For Grid Naming Service (GNS)

If you enable Grid Naming Service (GNS), then name resolution requests to the cluster are delegated to the GNS, which is listening on the GNS virtual IP address. The domain name server (DNS) must be configured to delegate resolution requests for cluster names (any names in the subdomain delegated to the cluster) to the GNS. When a request comes to the domain, GNS processes the requests and responds with the appropriate addresses for the name requested. To use GNS, you must specify a static IP address for the GNS VIP address.

IP Name and Address Requirements for Manual Configuration of Cluster

For Oracle Flex Clusters, configure static cluster node names and addresses if you do not enable GNS.

IP Address Requirements for Static Clusters

Public and virtual IP names must conform with the RFC 952 standard, which allows alphanumeric characters and hyphens ("-"), but does not allow underscores ("_").

Oracle Clusterware manages private IP addresses in the private subnet on interfaces you identify as private during the installation interview.

Public IP Address Requirements

The cluster must have a public IP address for each node, with the following characteristics:

- Static IP address
- Configured before installation for each node, and resolvable to that node before installation
- On the same subnet as all other public IP addresses, VIP addresses, and SCAN addresses in the cluster

Virtual IP Address Requirements

The cluster must have a virtual IP address for each node, with the following characteristics:

- Static IP address
- Configured before installation for each node, but not currently in use
- On the same subnet as all other public IP addresses, VIP addresses, and SCAN addresses in the cluster

Single Client Access Name Requirements

The cluster must have a Single Client Access Name (SCAN) for the cluster, with the following characteristics:

- Three static IP addresses configured on the domain name server (DNS) before installation so that the three IP addresses are associated with the name provided as the SCAN, and all three addresses are returned in random order by the DNS to the requestor
- Configured before installation in the DNS to resolve to addresses that are not currently in use
- Given addresses on the same subnet as all other public IP addresses, VIP addresses, and SCAN addresses in the cluster
- Given a name conforms with the RFC 952 standard, which allows alphanumeric characters and hyphens ("-"), but does not allow underscores ("_")

Private IP Address Requirements

The cluster must have a private IP address for each node, with the following characteristics:

- Static IP address
- Configured before installation, but on a separate, private network, with its own subnet, that is not resolvable except by other cluster member nodes

The SCAN is a name used to provide service access for clients to the cluster. Because the SCAN is associated with the cluster as a whole, rather than to a particular node, the SCAN makes it possible to add or remove nodes from the cluster without needing to reconfigure clients. It also adds location independence for the databases, so that client configuration does not have to depend on which nodes are running a particular database. Clients can continue to access the cluster in the same way as with previous releases, but Oracle recommends that clients accessing the cluster use the SCAN.

Note:

The SCAN and cluster name are entered in separate fields during installation, so cluster name requirements do not apply to the SCAN name.

Oracle strongly recommends that you do not configure SCAN VIP addresses in the hosts file. Use DNS resolution for SCAN VIPs. If you use the hosts file to resolve SCANS, then the SCAN can resolve to one IP address only.

Configuring SCANS in a DNS or a hosts file is the only supported configuration. Configuring SCANS in a Network Information Service (NIS) is not supported.

Confirming the DNS Configuration for SCAN

Use the `nslookup` command to confirm that the DNS is correctly associating the SCAN with the addresses.

Note:

All name servers in the DNS configuration for a cluster must resolve to all host names used in the cluster, such as cluster node host name, VIP host name, and SCAN host name.

The following example shows how to use the `nslookup` command to confirm that the DNS is correctly associating the SCAN with the addresses:

```
root@node1]$ nslookup mycluster-scan
Server:         dns.example.com
Address:        192.0.2.001

Name:   mycluster-scan.example.com
Address: 192.0.2.201
Name:   mycluster-scan.example.com
Address: 192.0.2.202
Name:   mycluster-scan.example.com
Address: 192.0.2.203
```

After installation, when a client sends a request to the cluster, the Oracle Clusterware SCAN listeners redirect client requests to servers in the cluster.

Oracle strongly recommends that you do not configure SCAN VIP addresses in the hosts file. Use DNS resolution for SCAN VIPs. If you use the hosts file to resolve SCANS, then the SCAN can resolve to one IP address only.

Configuring SCANS in a DNS or a hosts file is the only supported configuration. Configuring SCANS in a Network Information Service (NIS) is not supported.

Broadcast Requirements for Networks Used by Oracle Grid Infrastructure

Broadcast communications (ARP and UDP) must work properly across all the public and private interfaces configured for use by Oracle Grid Infrastructure.

The broadcast must work across any configured VLANs as used by the public or private interfaces.

When configuring public and private network interfaces for Oracle RAC, you must enable Address Resolution Protocol (ARP). Highly Available IP (HAIP) addresses do not require ARP on the public network, but for VIP failover, you need to enable ARP. Do not configure `NOARP`.

Multicast Requirements for Networks Used by Oracle Grid Infrastructure

For each cluster member node, the Oracle mDNS daemon uses multicasting on all interfaces to communicate with other nodes in the cluster.

Multicast Requirements for Networks Used by Oracle Grid Infrastructure

Multicasting is required on the private interconnect. For this reason, at a minimum, you must enable multicasting for the cluster:

- Across the broadcast domain as defined for the private interconnect
- On the IP address subnet ranges 224.0.0.0/24 and optionally 230.0.1.0/24

You do not need to enable multicast communications across routers.

Domain Delegation to Grid Naming Service

If you are configuring Grid Naming Service (GNS) for a standard cluster, then before installing Oracle Grid Infrastructure you must configure DNS to send to GNS any name resolution requests for the subdomain served by GNS.

Note:

The Highly Available Grid Naming Service feature of Grid Naming Service (GNS) in Oracle Grid Infrastructure is deprecated in Oracle Database 23ai. The highly-available GNS provides the ability to run multiple GNS instances in a multi-cluster environment with different roles. This feature is being deprecated. There is no replacement.

- [Choosing a Subdomain Name for Use with Grid Naming Service](#)
To implement GNS, your network administrator must configure the DNS to set up a domain for the cluster, and delegate resolution of that domain to the GNS VIP.

Choosing a Subdomain Name for Use with Grid Naming Service

To implement GNS, your network administrator must configure the DNS to set up a domain for the cluster, and delegate resolution of that domain to the GNS VIP.

Note:

The Highly Available Grid Naming Service feature of Grid Naming Service (GNS) in Oracle Grid Infrastructure is deprecated in Oracle Database 23ai.

Requirements for Choosing a Subdomain Name for Use with GNS

You can use a separate domain, or you can create a subdomain of an existing domain for the cluster. The subdomain name can be any supported DNS name such as `sales-cluster.rac.com`.

Oracle recommends that the subdomain name is distinct from your corporate domain. For example, if your corporate domain is `mycorp.example.com`, the subdomain for GNS might be `rac-gns.mycorp.example.com`.

If the subdomain is not distinct, then it should be for the exclusive use of GNS. For example, if you delegate the subdomain `mydomain.example.com` to GNS, then there should be no other domains that share it such as `lab1.mydomain.example.com`.

Configuration Requirements for Oracle Flex Clusters

Understand Oracle Flex Clusters and their configuration requirements.

- [Understanding Oracle Flex Clusters](#)
Starting with Oracle Grid Infrastructure 12c Release 2 (12.2), Oracle Grid Infrastructure cluster configurations are Oracle Flex Clusters deployments.

- [About Oracle Flex ASM Clusters Networks](#)
Oracle ASM is configured as part of an Oracle Flex Cluster installation within Oracle Grid Infrastructure to provide storage services.
- [General Requirements for Oracle Flex Cluster Configuration](#)
Review this information about network requirements for Oracle Flex Cluster configuration.
- [Oracle Flex Cluster DHCP-Assigned Virtual IP \(VIP\) Addresses](#)
Configure cluster node VIP names for all the cluster nodes.
- [Oracle Flex Cluster Manually-Assigned Addresses](#)
Review this information to manually assign cluster node VIP names for the cluster nodes.

Understanding Oracle Flex Clusters

Starting with Oracle Grid Infrastructure 12c Release 2 (12.2), Oracle Grid Infrastructure cluster configurations are Oracle Flex Clusters deployments.

Oracle Grid Infrastructure installed in an Oracle Flex Cluster configuration is a scalable, dynamic, robust network of nodes. Oracle Flex Clusters provide a platform for Oracle Real Application Clusters databases with large numbers of nodes, to support massive parallel query operations. Oracle Flex Clusters also provide a platform for other service deployments that require coordination and automation for high availability.

All nodes in an Oracle Flex Cluster belong to a single Oracle Grid Infrastructure cluster. This architecture centralizes policy decisions for deployment of resources based on application needs, to account for various service levels, loads, failure responses, and recovery. Nodes in Oracle Flex Clusters are tightly connected, and have direct access to shared storage

About Oracle Flex ASM Clusters Networks

Oracle ASM is configured as part of an Oracle Flex Cluster installation within Oracle Grid Infrastructure to provide storage services.

Oracle Flex ASM enables an Oracle ASM instance to run on a separate physical server from the database servers. Many Oracle ASM instances can be clustered to support numerous database clients. Each Oracle Flex ASM cluster has its own name that is globally unique within the enterprise.

You can consolidate all the storage requirements into a single set of disk groups. All these disk groups are managed by a small set of Oracle ASM instances running in a single Oracle Flex Cluster.

Every Oracle Flex ASM cluster has one or more cluster nodes on which Oracle ASM instances are running.

Oracle Flex ASM can use either the same private networks as Oracle Clusterware, or use its own dedicated private networks. Each network can be classified `PUBLIC`, `ASM & PRIVATE`, `PRIVATE`, or `ASM`.

The Oracle ASM network can be configured during installation, or configured or modified after installation.

About Oracle Flex ASM Cluster Configuration on Cluster Nodes

Oracle Flex ASM cluster nodes can be configured with the following characteristics:

- Are similar to prior release Oracle Grid Infrastructure cluster member nodes, as all servers configured with the cluster node role are peers.

- Have direct connections to the Oracle ASM disks.
- Run a Direct ASM client process.
- Run an Oracle ASM Filter Driver, part of whose function is to provide cluster fencing security for the Oracle Flex ASM cluster.
- Respond to service requests delegated to them through the global Oracle ASM listener configured for the Oracle Flex ASM cluster, which designates three of the Oracle Flex ASM cluster member node listeners as remote listeners for the Oracle Flex ASM cluster.
- Can provide database clients that are running on nodes of the Oracle ASM cluster remote access to Oracle ASM for metadata, and allow database clients to perform block I/O operations directly to Oracle ASM disks. The hosts running the Oracle ASM server and the remote database client must both be cluster nodes.

Related Topics

- *Oracle Automatic Storage Management Administrator's Guide*

General Requirements for Oracle Flex Cluster Configuration

Review this information about network requirements for Oracle Flex Cluster configuration.

Network Requirements for Oracle Flex Cluster Configuration

- You must use Grid Naming Service (GNS) with an Oracle Flex Cluster deployment.
- You must configure the GNS VIP as a static IP address.
- All public network addresses, whether assigned manually or automatically, must be in the same subnet range.
- All Oracle Flex Cluster addresses must be either static IP addresses, DHCP addresses assigned through DHCP (IPv4) or autoconfiguration addresses assigned through an autoconfiguration service (IPv6), registered in the cluster through GNS.

Oracle Flex Cluster DHCP-Assigned Virtual IP (VIP) Addresses

Configure cluster node VIP names for all the cluster nodes.

Requirements for DHCP-Assigned VIP Addresses

If you want to configure DHCP-assigned VIPs, then during installation, configure cluster node VIP names as follows:

- **Automatically Assigned Names:** Select the **Configure nodes Virtual IPs assigned by the Dynamic Networks** option to allow the installer to assign names to VIP addresses generated through DHCP automatically. Addresses are assigned through DHCP, and resolved by GNS. Oracle Clusterware sends DHCP requests with `client ID nodename-vip` and without a MAC address. You can verify the availability of DHCP addresses using the `cluvfy comp dhcp` command.

Oracle Flex Cluster Manually-Assigned Addresses

Review this information to manually assign cluster node VIP names for the cluster nodes.

Requirements for Manually-Assigned Addresses

If you choose to configure manually-assigned VIPs, then during installation, you must configure cluster node VIP names for all cluster nodes using one of the following options:

- **Manual Names:** Enter the host name and virtual IP name for each node manually. The names you provide must resolve to addresses configured on the DNS. Names must conform with the RFC 952 standard, which allows alphanumeric characters and hyphens ("-"), but does not allow underscores ("_").
- **Automatically Assigned Names:** Enter string variables for values corresponding to host names that you have configured on the DNS. String variables allow you to assign a large number of names rapidly during installation. Configure addresses on the DNS with the following characteristics:
 - **Hostname prefix:** a prefix string used in each address configured on the DNS for use by cluster member nodes. For example: `mycloud`.
 - **Range:** A range of numbers to be assigned to the cluster member nodes, consisting of a starting node number and an ending node number, designating the end of the range. For example: `001` and `999`.
 - **Node name suffix:** A suffix added after the end of a range number to a public node name. For example: `nd`.
 - **VIP name suffix:** A suffix added after the end of a virtual IP node name. For example: `-vip`.

Syntax

You can create manual addresses using alphanumeric strings.

Example 5-1 Examples of Manually-Assigned Addresses

```
mycloud001nd; mycloud046nd; mycloud046-vip; mycloud348nd; mycloud784-vip
```

Grid Naming Service Cluster Configuration Example

Review this example to understand Grid Naming Service configuration.

Note:

The Highly Available Grid Naming Service feature of Grid Naming Service (GNS) in Oracle Grid Infrastructure is deprecated in Oracle Database 23ai.

To use GNS, you must specify a static IP address for the GNS VIP address, and you must have a subdomain configured on your DNS to delegate resolution for that subdomain to the static GNS IP address.

As nodes are added to the cluster, your organization's DHCP server can provide addresses for these nodes dynamically. These addresses are then registered automatically in GNS, and GNS provides resolution within the subdomain to cluster node addresses registered with GNS.

Because allocation and configuration of addresses is performed automatically with GNS, no further configuration is required. Oracle Clusterware provides dynamic network configuration as nodes are added to or removed from the cluster. The following example is provided only for information.

With IPv6 networks, the IPv6 auto configuration feature assigns IP addresses and no DHCP server is required.

With a two node cluster where you have defined the GNS VIP, after installation you might have a configuration similar to the following for a two-node cluster, where the cluster name is `mycluster`, the GNS parent domain is `gns.example.com`, the subdomain is `cluster01.example.com`, the `192.0.2` portion of the IP addresses represents the cluster public IP address subdomain, and `192.168` represents the private IP address subdomain:

Table 5-1 Grid Naming Service Cluster Configuration Example

Identity	Home Node	Host Node	Given Name	Type	Address	Address Assigned By	Resolved By
GNS VIP	None	Selected by Oracle Clusterware	mycluster-gns-vip.example.com	virtual	192.0.2.1	Fixed by net administrator	DNS
Node 1 Public	Node 1	node1	node1	public	192.0.2.101	Fixed	GNS
Node 1 VIP	Node 1	Selected by Oracle Clusterware	node1-vip	virtual	192.0.2.104	DHCP	GNS
Node 1 Private	Node 1	node1	node1-priv	private	192.168.0.1	Fixed or DHCP	GNS
Node 2 Public	Node 2	node2	node2	public	192.0.2.102	Fixed	GNS
Node 2 VIP	Node 2	Selected by Oracle Clusterware	node2-vip	virtual	192.0.2.105	DHCP	GNS
Node 2 Private	Node 2	node2	node2-priv	private	192.168.0.2	Fixed or DHCP	GNS
SCAN VIP 1	none	Selected by Oracle Clusterware	mycluster-scan.mycluster.cluster01.example.com	virtual	192.0.2.201	DHCP	GNS
SCAN VIP 2	none	Selected by Oracle Clusterware	mycluster-scan.mycluster.cluster01.example.com	virtual	192.0.2.202	DHCP	GNS
SCAN VIP 3	none	Selected by Oracle Clusterware	mycluster-scan.mycluster.cluster01.example.com	virtual	192.0.2.203	DHCP	GNS

Manual IP Address Configuration Example

If you choose not to use GNS, then before installation you must configure public, virtual, and private IP addresses.

Check that the default gateway can be accessed by a ping command. To find the default gateway, use the `route` command, as described in your operating system's help utility.

For example, with a two-node cluster where each node has one public and one private interface, and you have defined a SCAN domain address to resolve on your DNS to one of three IP addresses, you might have the configuration shown in the following table for your network interfaces:

Table 5-2 Manual Network Configuration Example

Identity	Home Node	Host Node	Given Name	Type	Address	Address Assigned By	Resolved By
Node 1 Public	Node 1	node1	node1	public	192.0.2.101	Fixed	DNS
Node 1 VIP	Node 1	Selected by Oracle Clusterware	node1-vip	virtual	192.0.2.104	Fixed	DNS and hosts file
Node 1 Private	Node 1	node1	node1-priv	private	192.168.0.1	Fixed	DNS and hosts file, or none
Node 2 Public	Node 2	node2	node2	public	192.0.2.102	Fixed	DNS
Node 2 VIP	Node 2	Selected by Oracle Clusterware	node2-vip	virtual	192.0.2.105	Fixed	DNS and hosts file
Node 2 Private	Node 2	node2	node2-priv	private	192.168.0.2	Fixed	DNS and hosts file, or none
SCAN VIP 1	none	Selected by Oracle Clusterware	mycluster-scan	virtual	192.0.2.201	Fixed	DNS
SCAN VIP 2	none	Selected by Oracle Clusterware	mycluster-scan	virtual	192.0.2.202	Fixed	DNS
SCAN VIP 3	none	Selected by Oracle Clusterware	mycluster-scan	virtual	192.0.2.203	Fixed	DNS

You do not need to provide a private name for the interconnect. If you want name resolution for the interconnect, then you can configure private IP names in the hosts file or the DNS. However, Oracle Clusterware assigns interconnect addresses on the interface defined during installation as the private interface (`eth1`, for example), and to the subnet used for the private subnet.

The addresses to which the SCAN resolves are assigned by Oracle Clusterware, so they are not fixed to a particular node. To enable VIP failover, the configuration shown in the preceding table defines the SCAN addresses and the public and VIP addresses of both nodes on the same subnet, `192.0.2.0/24`.



Note:

All host names must conform to the RFC-952 standard, which permits alphanumeric characters, but does not allow underscores ("_").

Network Interface Configuration Options

During installation, you are asked to identify the planned use for each network adapter (or network interface) that Oracle Universal Installer (OUI) detects on your cluster node.

Each NIC can be configured to perform only one of the following roles:

- Public
- Private
- ASM
- ASM & Private
- Do Not Use

Network Interface Configuration Options

You must use the same private adapters for both Oracle Clusterware and Oracle RAC. The precise configuration you choose for your network depends on the size and use of the cluster you want to configure, and the level of availability you require. Network interfaces must be at least 1 GbE, with 10 GbE recommended. Alternatively, use InfiniBand for the interconnect.

If certified Network-attached Storage (NAS) is used for Oracle RAC and this storage is connected through Ethernet-based networks, then you must have a third network interface for NAS I/O. Failing to provide three separate interfaces in this case can cause performance and stability problems under load.

Redundant interconnect usage cannot protect network adapters used for public communication. If you require high availability or load balancing for public adapters, then use a third party solution. Typically, bonding, trunking or similar technologies can be used for this purpose.

You can enable redundant interconnect usage for the private network by selecting multiple network adapters to use as private adapters. Redundant interconnect usage creates a redundant interconnect when you identify more than one network adapter as private.

Multiple Private Interconnects and Oracle Linux

Review this information for settings for the `rp_filter` parameter for Oracle RAC systems that use multiple NICs for the private interconnect.

With Oracle Linux kernel 2.6.31, which also includes Oracle Unbreakable Enterprise Kernel 2.6.32, a bug has been fixed in the Reverse Path Filtering. As a consequence of this correction, Oracle RAC systems that use multiple NICs for the private interconnect now require specific settings for the `rp_filter` parameter. This requirement also applies to all Exadata systems that are running Linux kernel 2.6.32 and above. Without these `rp_filter` parameter settings systems, interconnect packets can be blocked or discarded.

The `rp_filter` values set the Reverse Path filter to no filtering (0), to strict filtering (1), or to loose filtering (2). Set the `rp_filter` value for the private interconnects to either 0 or 2. Setting the private interconnect NIC to 1 can cause connection issues on the private interconnect. It is not considered unsafe to disable or relax this filtering, because the private interconnect should be on a private and isolated network.

For example, where `eth1` and `eth2` are the private interconnect NICs, and `eth0` is the public network NIC, set the `rp_filter` of the private address to 2 (loose filtering), the public address to 1 (strict filtering), using the following entries in `/etc/sysctl.conf`:

```
net.ipv4.conf.eth2.rp_filter = 2
net.ipv4.conf.eth1.rp_filter = 2
net.ipv4.conf.eth0.rp_filter = 1
```



See Also:

<https://support.oracle.com/rs?type=doc&id=1286796.1> for more information about `rp_filter` for multiple private interconnects and Linux Kernel 2.6.32+

Creating SCAN Client Data File

Generate a SCAN client data file and copy the file to the SCAN client cluster member node on which you are installing Oracle Grid Infrastructure.

1. As the `grid` user, create a SCAN listener that is exclusive to this shared SCAN cluster.

```
$ srvctl add scan_listener -clientcluster cluster_name
```

2. As the `root` user, create a new Oracle Notification Service (ONS) resource that is specific to the server cluster.

```
# srvctl add ons -clientcluster cluster_name
```

The `srvctl add ons` command assigns an ID to the SCAN.

3. As the `grid` user, export the SCAN listener to the client cluster.

```
$ srvctl export scan_listener -clientcluster cluster_name -clientdata
file_name
```

4. Export the ONS resource to the client cluster.

```
$ srvctl export ons -clientcluster cluster_name -clientdata file_name
```

5. Modify the SCAN listener configuration.

```
$ srvctl modify scan_listener -clientcluster cluster_name -invitednodes
new_cluster_nodes -update
```

6. Start the SCAN listener.

```
$ srvctl start scan_listener -clientcluster cluster_name
```

6

Configuring Users, Groups and Environments for Oracle Grid Infrastructure and Oracle Database

Before installation, create operating system groups and users, and configure user environments.

- [Creating Groups, Users and Paths for Oracle Grid Infrastructure](#)
Log in as `root`, and use the following instructions to locate or create the Oracle Inventory group, and create a Oracle Grid Infrastructure software owner, and Oracle home directories.
- [Oracle Installations with Standard and Job Role Separation Groups and Users](#)
A job role separation configuration of Oracle Database and Oracle ASM is a configuration with groups and users to provide separate groups for operating system authentication.
- [Creating Operating System Privileges Groups](#)
The following sections describe how to create operating system groups for Oracle Grid Infrastructure and Oracle Database:
- [Creating Operating System Oracle Installation User Accounts](#)
Before starting installation, create Oracle software owner user accounts, and configure their environments.
- [Configuring Grid Infrastructure Software Owner User Environments](#)
Understand the software owner user environments to configure before installing Oracle Grid Infrastructure.
- [Enabling Intelligent Platform Management Interface \(IPMI\)](#)
Intelligent Platform Management Interface (IPMI) provides a set of common interfaces to computer hardware and firmware that system administrators can use to monitor system health and manage the system.

Creating Groups, Users and Paths for Oracle Grid Infrastructure

Log in as `root`, and use the following instructions to locate or create the Oracle Inventory group, and create a Oracle Grid Infrastructure software owner, and Oracle home directories.

Oracle software installations require an installation owner, an Oracle Inventory group, which is the primary group of all Oracle installation owners, and at least one group designated as a system privileges group. Review group and user options with your system administrator.

- [Determining If an Oracle Inventory and Oracle Inventory Group Exist](#)
Determine if you have an existing Oracle central inventory, and ensure that you use the same Oracle Inventory for all Oracle software installations. Also, ensure that all Oracle software users you intend to use for installation have permissions to write to this directory.
- [Creating the Oracle Inventory Group If an Oracle Inventory Does Not Exist](#)
If the `oraInst.loc` file does not exist, then create the Oracle Inventory group.

- [About Oracle Installation Owner Accounts](#)
Select or create an Oracle installation owner for your installation, depending on the group and user management plan you want to use for your installations.
- [Restrictions for Oracle Software Installation Owners](#)
Review the following restrictions for users created to own Oracle software.
- [Identifying an Oracle Software Owner User Account](#)
You must create at least one software owner user account the first time you install Oracle software on the system. Either use an existing Oracle software user account, or create an Oracle software owner user account for your installation.
- [About the Oracle Base Directory for the grid User](#)
Review this information about creating the Oracle base directory on each cluster node.
- [About the Oracle Home Directory for Oracle Grid Infrastructure Software](#)
Review this information about creating the Oracle home directory location on each cluster node.
- [About Creating the Oracle Home and Oracle Base Directory](#)
Create Grid home and Oracle base home directories on each cluster node.

Determining If an Oracle Inventory and Oracle Inventory Group Exist

Determine if you have an existing Oracle central inventory, and ensure that you use the same Oracle Inventory for all Oracle software installations. Also, ensure that all Oracle software users you intend to use for installation have permissions to write to this directory.

When you install Oracle software on the system for the first time, OUI creates the `oraInst.loc` file. This file identifies the name of the Oracle Inventory group (by default, `oinstall`), and the path of the Oracle central inventory directory. If you have an existing Oracle central inventory, then ensure that you use the same Oracle Inventory for all Oracle software installations, and ensure that all Oracle software users you intend to use for installation have permissions to write to this directory.

```
oraInst.loccentral_inventory_locationgroup
```

```
inventory_loc=central_inventory_location  
inst_group=group
```

Use the `more` command to determine if you have an Oracle central inventory on your system. For example:

```
# more /etc/oraInst.loc  
  
inventory_loc=/u01/app/oraInventory  
inst_group=oinstall
```

Use the command `grep groupname /etc/group` to confirm that the group specified as the Oracle Inventory group still exists on the system. For example:

```
$ grep oinstall /etc/group  
oinstall:x:54321:grid,oracle
```

 **Note:**

Do not put the `oraInventory` directory under the Oracle base directory for a new installation, because that can result in user permission errors for other installations.

Creating the Oracle Inventory Group If an Oracle Inventory Does Not Exist

If the `oraInst.loc` file does not exist, then create the Oracle Inventory group.

Members of the OINSTALL group are granted privileges to write to the Oracle central inventory (`oraInventory`), and other system privileges for Oracle installation owner users.

An Oracle installation owner should always have the group you want to have designated as the OINSTALL group (`oinstall`) as its primary group. Ensure that this group is available as the primary group for all planned Oracle software installation owners. By default, if an `oraInst.loc` file does not exist and an Oracle central inventory (`oraInventory`) is not identified, then the installer designates the primary group of the installation owner running the installation as the OINSTALL group.

 **Note:**

For installations on Oracle Clusterware, group and user IDs must be identical on all nodes in the cluster. Ensure that the group and user IDs you want to use are available on each cluster member node, and confirm that the primary group for each Oracle Grid Infrastructure for a cluster installation owner has the same name and group ID.

The following example creates the `oraInventory` group `oinstall`, with the group ID number 54321.

```
# /usr/sbin/groupadd -g 54321 oinstall
```

About Oracle Installation Owner Accounts

Select or create an Oracle installation owner for your installation, depending on the group and user management plan you want to use for your installations.

You must create a software owner for your installation in the following circumstances:

- If an Oracle software owner user does not exist; for example, if this is the first installation of Oracle software on the system.
- If an Oracle software owner user exists, but you want to use a different operating system user, with different group membership, to separate Oracle Grid Infrastructure administrative privileges from Oracle Database administrative privileges.

In Oracle documentation, a user created to own only Oracle Grid Infrastructure software installations is called the Grid user (`grid`). This user owns both the Oracle Clusterware and Oracle Automatic Storage Management binaries. A user created to own either all Oracle installations, or one or more Oracle database installations, is called the Oracle user (`oracle`). You can have only one Oracle Grid Infrastructure installation owner, but you can have different Oracle users to own different installations.

Oracle software owners must have the Oracle Inventory group as their primary group, so that each Oracle software installation owner can write to the central inventory (`oraInventory`), and so that OCR and Oracle Clusterware resource permissions are set correctly. The database software owner must also have the OSDBA group and (if you create them) the OSOPER, OSBACKUPDBA, OSDGDBA, OSRACDBA, and OSKMDBA groups as secondary groups.

Restrictions for Oracle Software Installation Owners

Review the following restrictions for users created to own Oracle software.

- If you intend to use multiple Oracle software owners for different Oracle Database homes, then Oracle recommends that you create a separate software owner for Oracle Grid Infrastructure software (Oracle Clusterware and Oracle ASM), and use that owner to run the Oracle Grid Infrastructure installation.
- During installation, SSH must be set up between cluster member nodes. SSH can be set up automatically by Oracle Universal Installer (the installer). To enable SSH to be set up automatically, create Oracle installation owners without any `stty` commands in their profiles, and remove other security measures that are triggered during a login that generate messages to the terminal. These messages, mail checks, and other displays prevent Oracle software installation owner accounts from using the SSH configuration script that is built into the installer. If they are not disabled, then SSH must be configured manually before an installation can be run.
- If you plan to install Oracle Database or Oracle RAC, then Oracle recommends that you create separate users for the Oracle Grid Infrastructure and the Oracle Database installations. If you use one installation owner, then when you want to perform administration tasks, you must change the value for `$ORACLE_HOME` to the instance you want to administer (Oracle ASM, in the Oracle Grid Infrastructure home, or the database in the Oracle home), using command syntax such as the following example, where `/u01/app/23.0.0/grid` is the Oracle Grid Infrastructure home:

```
$ export ORACLE_HOME=/u01/app/23.0.0/grid
```

- If you try to administer an Oracle home or Grid home instance using `sqlplus`, `lsnrctl`, or `asmcmd` commands while the environment variable `$ORACLE_HOME` is set to a different Oracle home or Grid home path, then you encounter errors. For example, when you start `SRVCTL` from a database home, `$ORACLE_HOME` should be set to that database home, or `SRVCTL` fails. The exception is when you are using `SRVCTL` in the Oracle Grid Infrastructure home. In that case, `$ORACLE_HOME` is ignored, and the Oracle home environment variable does not affect `SRVCTL` commands. In all other cases, you must change `$ORACLE_HOME` to the instance that you want to administer.
- To create separate Oracle software owners and separate operating system privileges groups for different Oracle software installations, note that each of these users must have the Oracle central inventory group (`oraInventory` group) as their primary group. Members of this group are granted the OINSTALL system privileges to write to the Oracle central inventory (`oraInventory`) directory, and are also granted permissions for various Oracle Clusterware resources, OCR keys, directories in the Oracle Clusterware home to which DBAs need write access, and other necessary privileges. Members of this group are also granted execute permissions to start and stop Clusterware infrastructure resources and databases. In Oracle documentation, this group is represented as `oinstall` in code examples.
- Each Oracle software owner must be a member of the same central inventory `oraInventory` group, and they must have this group as their primary group, so that all Oracle software installation owners share the same OINSTALL system privileges. Oracle

recommends that you do not have more than one central inventory for Oracle installations. If an Oracle software owner has a different central inventory group, then you may corrupt the central inventory.

Identifying an Oracle Software Owner User Account

You must create at least one software owner user account the first time you install Oracle software on the system. Either use an existing Oracle software user account, or create an Oracle software owner user account for your installation.

To use an existing user account, obtain the name of an existing Oracle installation owner from your system administrator. Confirm that the existing owner is a member of the Oracle Inventory group.

For example, if you know that the name of the Oracle Inventory group is `oinstall`, then an Oracle software owner should be listed as a member of `oinstall`:

```
$ grep "oinstall" /etc/group
oinstall:x:54321:grid,oracle
```

You can then use the `id` command to verify that the Oracle installation owners you intend to use have the Oracle Inventory group as their primary group. For example:

```
$ id oracle
uid=54321(oracle) gid=54321(oinstall) groups=54321(oinstall),54322(dba),
54323(oper),54324(backupdba),54325(dgdba),54326(kmdba),54327(asmdba),54330(rac
dba)
```

```
$ id grid
uid=54331(grid) gid=54321(oinstall) groups=54321(oinstall),54322(dba),
54327(asmdba),54328(asmoper),54329(asmadmin),54330(racdba)
```

For Oracle Restart installations, to successfully install Oracle Database, ensure that the `grid` user is a member of the `racdba` group.

After you create operating system groups, create or modify Oracle user accounts in accordance with your operating system authentication planning.

About the Oracle Base Directory for the grid User

Review this information about creating the Oracle base directory on each cluster node.

The Oracle base directory for the Oracle Grid Infrastructure installation is the location where diagnostic and administrative logs, and other logs associated with Oracle ASM and Oracle Clusterware are stored. For Oracle installations other than Oracle Grid Infrastructure for a cluster, it is also the location under which an Oracle home is placed.

However, in the case of an Oracle Grid Infrastructure installation, you must create a *different* path, so that the path for Oracle bases remains available for other Oracle installations.

For OUI to recognize the Oracle base path, it must be in the form `u[00-99][00-99]/app`, and it must be writable by any member of the `oraInventory` (`oinstall`) group. The OFA path for the

Oracle base is `u[00-99][00-99]/app/user`, where *user* is the name of the software installation owner. For example:

```
/u01/app/grid
```

**Note:**

Oracle home or Oracle base cannot be `symlinks`, nor can any of their parent directories, all the way to up to the `root` directory.

About the Oracle Home Directory for Oracle Grid Infrastructure Software

Review this information about creating the Oracle home directory location on each cluster node.

The Oracle home for Oracle Grid Infrastructure software (Grid home) should be located in a path that is different from the Oracle home directory paths for any other Oracle software. The Optimal Flexible Architecture guideline for a Grid home is to create a path in the form `/pm/v/u`, where *p* is a string constant, *m* is a unique fixed-length key (typically a two-digit number), *v* is the version of the software, and *u* is the installation owner of the Oracle Grid Infrastructure software (`grid` user). During Oracle Grid Infrastructure for a cluster installation, the path of the Grid home is changed to the `root` user, so any other users are unable to read, write, or run commands in that path. For example, to create a Grid home in the standard mount point path format `u[00-99][00-99]/app/release/grid`, where *release* is the release number of the Oracle Grid Infrastructure software, create the following path:

```
/u01/app/23.0.0/grid
```

**Note:**

Oracle home or Oracle base cannot be `symlinks`, nor can any of their parent directories, all the way to up to the `root` directory.

During installation, ownership of the entire path to the Grid home is changed to `root` (`/u01, /u01/app, /u01/app/23.0.0, /u01/app/23.0.0/grid`). If you do not create a unique path to the Grid home, then after the Grid install, you can encounter permission errors for other installations, including any existing installations under the same path. To avoid placing the application directory in the mount point under `root` ownership, you can create and select paths such as the following for the Grid home:

```
/u01/23.0.0/grid
```


 **Caution:**

For Oracle Grid Infrastructure for a cluster installations, note the following restrictions for the Oracle Grid Infrastructure binary home (Grid home directory for Oracle Grid Infrastructure):

- It must not be placed under one of the Oracle base directories, including the Oracle base directory of the Oracle Grid Infrastructure installation owner.
- It must not be placed in the home directory of an installation owner. These requirements are specific to Oracle Grid Infrastructure for a cluster installations.

Oracle Grid Infrastructure for a standalone server (Oracle Restart) can be installed under the Oracle base for the Oracle Database installation.

About Creating the Oracle Home and Oracle Base Directory

Create Grid home and Oracle base home directories on each cluster node.

Oracle recommends that you create Oracle Grid Infrastructure Grid home and Oracle base homes manually, particularly if you have separate Oracle Grid Infrastructure for a cluster and Oracle Database software owners, so that you can separate log files for the Oracle Grid Infrastructure installation owner in a separate Oracle base, and prevent accidental placement of the Grid home under an Oracle base path. For example:

```
# mkdir -p /u01/app/23.0.0/grid
# mkdir -p /u01/app/grid
# mkdir -p /u01/app/oracle
# chown -R grid:oinstall /u01
# chown oracle:oinstall /u01/app/oracle
# chmod -R 775 /u01/
```

 **Note:**

Placing Oracle Grid Infrastructure for a cluster binaries on a cluster file system is not supported.

If you plan to install an Oracle RAC home on a shared OCFS2 location, then you must upgrade OCFS2 to at least version 1.4.1, which supports shared writable maps.

Oracle recommends that you install Oracle Grid Infrastructure locally, on each cluster member node. Using a shared Grid home prevents rolling upgrades, and creates a single point of failure for the cluster.

Oracle home or Oracle base cannot be `symlinks`, nor can any of their parent directories, all the way to up to the `root` directory.

Related Topics

- [Optimal Flexible Architecture](#)
Oracle Optimal Flexible Architecture (OFA) rules are a set of configuration guidelines created to ensure well-organized Oracle installations, which simplifies administration, support and maintenance.

Oracle Installations with Standard and Job Role Separation Groups and Users

A job role separation configuration of Oracle Database and Oracle ASM is a configuration with groups and users to provide separate groups for operating system authentication.

Review the following sections to understand more about a Job Role Separation deployment:

- [About Oracle Installations with Job Role Separation](#)
Job role separation requires that you create different operating system groups for each set of system privileges that you grant through operating system authorization.
- [Standard Oracle Database Groups for Database Administrators](#)
Oracle Database has two standard administration groups: OSDBA, which is required, and OSOPER, which is optional.
- [Extended Oracle Database Groups for Job Role Separation](#)
Oracle Database provides an extended set of database groups to grant task-specific system privileges for database administration.
- [Creating an ASMSNMP User](#)
The `ASMSNMP` user is an Oracle ASM user with privileges to monitor Oracle ASM instances. You are prompted to provide a password for this user during installation.
- [Oracle Automatic Storage Management Groups for Job Role Separation](#)
Oracle Grid Infrastructure operating system groups provide their members task-specific system privileges to access and to administer Oracle Automatic Storage Management.

About Oracle Installations with Job Role Separation

Job role separation requires that you create different operating system groups for each set of system privileges that you grant through operating system authorization.

With Oracle Grid Infrastructure job role separation, Oracle ASM has separate operating system groups that provide operating system authorization for Oracle ASM system privileges for storage tier administration. This operating system authorization is separated from Oracle Database operating system authorization. In addition, the Oracle Grid Infrastructure installation owner provides operating system user authorization for modifications to Oracle Grid Infrastructure binaries.

With Oracle Database job role separation, each Oracle Database installation has separate operating system groups to provide authorization for system privileges on that Oracle Database. Multiple databases can, therefore, be installed on the cluster without sharing operating system authorization for system privileges. In addition, each Oracle software installation is owned by a separate installation owner, to provide operating system user authorization for modifications to Oracle Database binaries. Note that any Oracle software owner can start and stop all databases and shared Oracle Grid Infrastructure resources such as Oracle ASM or Virtual IP (VIP). Job role separation configuration enables database security, and does not restrict user roles in starting and stopping various Oracle Clusterware resources.

You can choose to create one administrative user and one group for operating system authentication for all system privileges on the storage and database tiers. For example, you can designate the `oracle` user to be the installation owner for all Oracle software, and designate `oinstall` to be the group whose members are granted all system privileges for Oracle Clusterware; all system privileges for Oracle ASM; all system privileges for all Oracle

Databases on the servers; and all `OINSTALL` system privileges for installation owners. This group must also be the Oracle Inventory group.

If you do not want to use role allocation groups, then Oracle strongly recommends that you use at least two groups:

- A system privileges group whose members are granted administrative system privileges, including `OSDBA`, `OSASM`, and other system privileges groups.
- An installation owner group (the `oraInventory` group) whose members are granted Oracle installation owner system privileges (the `OINSTALL` system privilege).

Note:

To configure users for installation that are on a network directory service such as Network Information Services (NIS), refer to your directory service documentation.

Related Topics

- *Oracle Database Administrator's Guide*
- *Oracle Automatic Storage Management Administrator's Guide*

Standard Oracle Database Groups for Database Administrators

Oracle Database has two standard administration groups: `OSDBA`, which is required, and `OSOPER`, which is optional.

- The `OSDBA` group (typically, `dba`)

You must create this group the first time you install Oracle Database software on the system. This group identifies operating system user accounts that have database administrative privileges (the `SYSDBA` privilege).

If you do not create separate `OSDBA`, `OSOPER`, and `OSASM` groups for the Oracle ASM instance, then operating system user accounts that have the `SYSOPER` and `SYSASM` privileges must be members of this group. The name used for this group in Oracle code examples is `dba`. If you do not designate a separate group as the `OSASM` group, then the `OSDBA` group you define is also by default the `OSASM` group.

- The `OSOPER` group for Oracle Database (typically, `oper`)

`OSOPER` grants the `OPERATOR` privilege to start up and shut down the database (the `SYSOPER` privilege). By default, members of the `OSDBA` group have all privileges granted by the `SYSOPER` privilege.

Extended Oracle Database Groups for Job Role Separation

Oracle Database provides an extended set of database groups to grant task-specific system privileges for database administration.

The extended set of Oracle Database system privileges groups are task-specific and less privileged than the `OSDBA/SYSDBA` system privileges. They are designed to provide privileges to carry out everyday database operations. Users granted these system privileges are also authorized through operating system group membership.

You do not have to create these specific group names, but during interactive and silent installation, you must assign operating system groups whose members are granted access to

these system privileges. You can assign the same group to provide authorization for these privileges, but Oracle recommends that you provide a unique group to designate each privilege.

The subset of OSDBA job role separation privileges and groups consist of the following:

- OSBACKUPDBA group for Oracle Database (typically, `backupdba`)
Create this group if you want a separate group of operating system users to have a limited set of database backup and recovery related administrative privileges (the `SYSBACKUP` privilege).
- OSDGDBA group for Oracle Data Guard (typically, `dgdba`)
Create this group if you want a separate group of operating system users to have a limited set of privileges to administer and monitor Oracle Data Guard (the `SYSDBG` privilege). To use this privilege, add the Oracle Database installation owners as members of this group.
- The OSKMDBA group for encryption key management (typically, `kmdba`)
Create this group if you want a separate group of operating system users to have a limited set of privileges for encryption key management (the `SYSKM` privilege). To use this privilege, add the Oracle Database installation owners as members of this group.
- The OSRACDBA group for Oracle Real Application Clusters Administration (typically, `racdba`)
Create this group if you want a separate group of operating system users to have a limited set of Oracle Real Application Clusters (RAC) administrative privileges (the `SYSRAC` privilege). To use this privilege:
 - Add the Oracle Database installation owners as members of this group.
 - For Oracle Restart configurations, if you have a separate Oracle Grid Infrastructure installation owner user (`grid`), then you must also add the `grid` user as a member of the OSRACDBA group of the database to enable Oracle Grid Infrastructure components to connect to the database.

Related Topics

- *Oracle Database Administrator's Guide*
- *Oracle Database Security Guide*

Creating an ASMSNMP User

The `ASMSNMP` user is an Oracle ASM user with privileges to monitor Oracle ASM instances. You are prompted to provide a password for this user during installation.

In addition to the `OSASM` group, whose members are granted the `SYSASM` system privilege to administer Oracle ASM, Oracle recommends that you create a less privileged user, `ASMSNMP`, and grant that user `SYSDBA` privileges to monitor the Oracle ASM instance. Oracle Enterprise Manager uses the `ASMSNMP` user to monitor Oracle ASM status.

During installation, you are prompted to provide a password for the `ASMSNMP` user. You can create an operating system authenticated user, or you can create an Oracle Database user called `asmsnmp`. In either case, grant the user `SYSDBA` privileges.

Oracle Automatic Storage Management Groups for Job Role Separation

Oracle Grid Infrastructure operating system groups provide their members task-specific system privileges to access and to administer Oracle Automatic Storage Management.

- The OSASM group for Oracle ASM Administration (typically, `asmadmin`)

Create this group as a separate group to separate administration privileges groups for Oracle ASM and Oracle Database administrators. Members of this group are granted the SYSASM system privileges to administer Oracle ASM. In Oracle documentation, the operating system group whose members are granted privileges is called the OSASM group, and in code examples, where there is a group specifically created to grant this privilege, it is referred to as `asmadmin`.

Oracle ASM can support multiple databases. If you have multiple databases on your system, and use multiple OSDBA groups so that you can provide separate SYSDBA privileges for each database, then you should create a group whose members are granted the OSASM/SYSASM administrative privileges, and create a grid infrastructure user (`grid`) that does not own a database installation, so that you separate Oracle Grid Infrastructure SYSASM administrative privileges from a database administrative privileges group.

Members of the OSASM group can use SQL to connect to an Oracle ASM instance as SYSASM using operating system authentication. The SYSASM privileges permit mounting and dismounting disk groups, and other storage administration tasks. SYSASM privileges provide no access privileges on an RDBMS instance.

If you do not designate a separate group as the OSASM group, but you do define an OSDBA group for database administration, then by default the OSDBA group you define is also defined as the OSASM group.

- The OSOPER group for Oracle ASM (typically, `asmoper`)

This is an optional group. Create this group if you want a separate group of operating system users to have a limited set of Oracle instance administrative privileges (the SYSOPER for ASM privilege), including starting up and stopping the Oracle ASM instance. By default, members of the OSASM group also have all privileges granted by the SYSOPER for ASM privilege.

Creating Operating System Privileges Groups

The following sections describe how to create operating system groups for Oracle Grid Infrastructure and Oracle Database:

- [Creating the OSASM Group](#)
If the OSASM group does not exist, or if you require a new OSASM group, then create it.
- [Creating the OSDBA for ASM Group](#)
You must designate a group as the OSDBA for ASM (`asmdba`) group during installation. Members of this group are also allowed to access the Oracle Automatic Storage Management (Oracle ASM) disk devices.
- [Creating the OSOPER for ASM Group](#)
You can choose to designate a group as the OSOPER for ASM group (`asmoper`) during installation. Members of this group are granted startup and shutdown privileges to Oracle Automatic Storage Management.
- [Creating the OSDBA Group for Database Installations](#)
Each Oracle Database requires an operating system group to be designated as the OSDBA group. Members of this group are granted the SYSDBA system privileges to administer the database.
- [Creating an OSOPER Group for Database Installations](#)
Create an OSOPER group only if you want to identify a group of operating system users with a limited set of database administrative privileges (SYSOPER operator privileges).

- [Creating the OSBACKUPDBA Group for Database Installations](#)
You must designate a group as the OSBACKUPDBA group during installation. Members of this group are granted the SYSBACKUP privileges to perform backup and recovery operations using RMAN or SQL*Plus.
- [Creating the OSDGDBA Group for Database Installations](#)
You must designate a group as the OSDGDBA group during installation. Members of this group are granted the SYSDG privileges to perform Data Guard operations.
- [Creating the OSKMDBA Group for Database Installations](#)
You must designate a group as the OSKMDBA group during installation. Members of this group are granted the SYSKM privileges to perform Transparent Data Encryption keystore operations.
- [Creating the OSRACDBA Group for Database Installations](#)
You must designate a group as the OSRACDBA group during database installation. Members of this group are granted the SYSRAC privileges to perform day-to-day administration of Oracle databases on an Oracle RAC cluster.

Creating the OSASM Group

If the OSASM group does not exist, or if you require a new OSASM group, then create it.

Use the group name `asmadmin` unless a group with that name already exists. For example:

```
# groupadd -g 54329 asmadmin
```

Creating the OSDBA for ASM Group

You must designate a group as the OSDBA for ASM (`asmdba`) group during installation. Members of this group are also allowed to access the Oracle Automatic Storage Management (Oracle ASM) disk devices.

The Oracle ASM disk devices should be owned by this group.

Create an OSDBA for ASM group using the group name `asmdba` unless a group with that name already exists:

```
# /usr/sbin/groupadd -g 54327 asmdba
```

Creating the OSOPER for ASM Group

You can choose to designate a group as the OSOPER for ASM group (`asmoper`) during installation. Members of this group are granted startup and shutdown privileges to Oracle Automatic Storage Management.

If you want to create an OSOPER for ASM group, use the group name `asmoper` unless a group with that name already exists:

```
# /usr/sbin/groupadd -g 54328 asmoper
```

Creating the OSDBA Group for Database Installations

Each Oracle Database requires an operating system group to be designated as the OSDBA group. Members of this group are granted the SYSDBA system privileges to administer the database.

You must create an OSDBA group in the following circumstances:

- An OSDBA group does not exist, for example, if this is the first installation of Oracle Database software on the system
- An OSDBA group exists, but you want to give a different group of operating system users database administrative privileges for a new Oracle Database installation

Create the OSDBA group using the group name `dba`, unless a group with that name already exists:

```
# /usr/sbin/groupadd -g 54322 dba
```

Creating an OSOPER Group for Database Installations

Create an OSOPER group only if you want to identify a group of operating system users with a limited set of database administrative privileges (SYSOPER operator privileges).

For most installations, it is sufficient to create only the OSDBA group. However, to use an OSOPER group, create it in the following circumstances:

- If an OSOPER group does not exist; for example, if this is the first installation of Oracle Database software on the system
- If an OSOPER group exists, but you want to give a different group of operating system users database operator privileges in a new Oracle installation

If the OSOPER group does not exist, or if you require a new OSOPER group, then create it. Use the group name `oper` unless a group with that name already exists. For example:

```
# groupadd -g 54323 oper
```

Creating the OSBACKUPDBA Group for Database Installations

You must designate a group as the OSBACKUPDBA group during installation. Members of this group are granted the SYSBACKUP privileges to perform backup and recovery operations using RMAN or SQL*Plus.

Create the OSBACKUPDBA group using the group name `backupdba`, unless a group with that name already exists:

```
# /usr/sbin/groupadd -g 54324 backupdba
```

Creating the OSDGDBA Group for Database Installations

You must designate a group as the OSDGDBA group during installation. Members of this group are granted the SYSDG privileges to perform Data Guard operations.

Create the OSDGDBA group using the group name `dgdba`, unless a group with that name already exists:

```
# /usr/sbin/groupadd -g 54325 dgdba
```

Creating the OSKMDBA Group for Database Installations

You must designate a group as the OSKMDBA group during installation. Members of this group are granted the SYSKM privileges to perform Transparent Data Encryption keystore operations.

If you want a separate group for Transparent Data Encryption, then create the OSKMDBA group using the group name `kmdba` unless a group with that name already exists:

```
# /usr/sbin/groupadd -g 54326 kmdba
```

Creating the OSRACDBA Group for Database Installations

You must designate a group as the OSRACDBA group during database installation. Members of this group are granted the SYSRAC privileges to perform day-to-day administration of Oracle databases on an Oracle RAC cluster.

Create the OSRACDBA group using the groups name `racdba` unless a group with that name already exists:

```
# /usr/sbin/groupadd -g 54330 racdba
```

Creating Operating System Oracle Installation User Accounts

Before starting installation, create Oracle software owner user accounts, and configure their environments.

Oracle software owner user accounts require resource settings and other environment configuration. To protect against accidents, Oracle recommends that you create one software installation owner account for each Oracle software program you install.

- [Creating an Oracle Software Owner User](#)
If the Oracle software owner user (`oracle` or `grid`) does not exist, or if you require a new Oracle software owner user, then create it as described in this section.
- [Modifying Oracle Owner User Groups](#)
If you have created an Oracle software installation owner account, but it is not a member of the groups you want to designate as the OSDBA, OSOPER, OSDBA for ASM, ASMAADMIN, or other system privileges group, then modify the group settings for that user before installation.

- [Identifying Existing User and Group IDs](#)
To create identical users and groups, you must identify the user ID and group IDs assigned them on the node where you created them, and then create the user and groups with the same name and ID on the other cluster nodes.
- [Creating Identical Database Users and Groups on Other Cluster Nodes](#)
Oracle software owner users and the Oracle Inventory, OSDBA, and OSOPER groups must exist and be identical on all cluster nodes.
- [Example of Creating Minimal Groups, Users, and Paths](#)
You can create a minimal operating system authentication configuration as described in this example.
- [Example of Creating Role-allocated Groups, Users, and Paths](#)
Understand this example of how to create role-allocated groups and users that is compliant with an Optimal Flexible Architecture (OFA) deployment.

Creating an Oracle Software Owner User

If the Oracle software owner user (`oracle` or `grid`) does not exist, or if you require a new Oracle software owner user, then create it as described in this section.

The following example shows how to create the user `oracle` with the user ID 54321; with the primary group `oinstall`; and with secondary groups `dba`, `asmdba`, `backupdba`, `dgdba`, `kmdba`, and `racdba`:

```
# /usr/sbin/useradd -u 54321 -g oinstall -G  
dba,asmdba,backupdba,dgdba,kmdba,racdba oracle
```

The following example shows how to create the user `grid` with the user ID 54331; with the primary group `oinstall`; and with secondary groups `dba`, `asmdba`, `backupdba`, `dgdba`, `kmdba`, and `racdba`:

```
# /usr/sbin/useradd -u 54331 -g oinstall -G  
dba,asmdba,backupdba,dgdba,kmdba,racdba grid
```

You must note the user ID number for installation users, because you need it during preinstallation.

For Oracle Grid Infrastructure installations, user IDs and group IDs must be identical on all candidate nodes.

Modifying Oracle Owner User Groups

If you have created an Oracle software installation owner account, but it is not a member of the groups you want to designate as the OSDBA, OSOPER, OSDBA for ASM, ASMADMIN, or other system privileges group, then modify the group settings for that user before installation.

Warning:

Each Oracle software owner must be a member of the same central inventory group. Do not modify the primary group of an existing Oracle software owner account, or designate different groups as the OINSTALL group. If Oracle software owner accounts have different groups as their primary group, then you can corrupt the central inventory.

During installation, the user who is installing the software should have the OINSTALL group as its primary group, and it must be a member of the operating system groups appropriate for your installation. For example:

```
# /usr/sbin/usermod -g oinstall -G
dba,asmdba,backupdba,dgdba,kmdba,racdba[,oper] oracle
```

Identifying Existing User and Group IDs

To create identical users and groups, you must identify the user ID and group IDs assigned them on the node where you created them, and then create the user and groups with the same name and ID on the other cluster nodes.

1. Enter a command similar to the following (in this case, to determine a user ID for the `oracle` user):

```
# id oracle
```

The output from this command is similar to the following:

```
uid=54321(oracle) gid=54421(oinstall)
groups=54322(dba),54323(oper),54327(asmdba)
```

2. From the output, identify the user ID (`uid`) for the user and the group identities (`gids`) for the groups to which it belongs.

Ensure that these ID numbers are identical on each node of the cluster. The user's primary group is listed after `gid`. Secondary groups are listed after `groups`.

Creating Identical Database Users and Groups on Other Cluster Nodes

Oracle software owner users and the Oracle Inventory, OSDBA, and OSOPER groups must exist and be identical on all cluster nodes.

To create users and groups on the other cluster nodes, repeat the following procedure on each node:

You must complete the following procedures only if you are using local users and groups. If you are using users and groups defined in a directory service such as NIS, then they are already identical on each cluster node.

1. Log in to the node as `root`.
2. Enter commands similar to the following to create the `asmadmin`, `asmdba`, `backupdba`, `dgdba`, `kmdba`, `asmoper`, `racdba`, and `oper` groups, and if not configured by the Oracle Database Preinstallation RPM or prior installations, then the `oinstall` and `dba` groups.

Use the `-g` option to specify the correct group ID for each group.

```
# groupadd -g 54421 oinstall
# groupadd -g 54322 dba
# groupadd -g 54323 oper
# groupadd -g 54324 backupdba
# groupadd -g 54325 dgdba
# groupadd -g 54326 kmdba
# groupadd -g 54327 asmdba
# groupadd -g 54328 asmoper
# groupadd -g 54329 asmadmin
# groupadd -g 54330 racdba
```

 **Note:**

You are not required to use the UIDs and GIDs in this example. If a group already exists, then use the `groupmod` command to modify it if necessary. If you cannot use the same group ID for a particular group on a node, then view the `/etc/group` file on all nodes to identify a group ID that is available on every node. You must then change the group ID on all nodes to the same group ID.

3. To create the Oracle Grid Infrastructure (`grid`) user, enter a command similar to the following:

```
# useradd -u 54322 -g oinstall -G asmadmin,asmdba,racdba grid
```

- The `-u` option specifies the user ID, which must be the user ID that you identified earlier.
- The `-g` option specifies the primary group for the Grid user, which must be the Oracle Inventory group (OINSTALL), which grants the OINSTALL system privileges. In this example, the OINSTALL group is `oinstall`.
- The `-G` option specifies the secondary groups. The Grid user must be a member of the OSASM group (`asmadmin`) and the OSDBA for ASM group (`asmdba`).

 **Note:**

If the user already exists, then use the `usermod` command to modify it if necessary. If you cannot use the same user ID for the user on every node, then view the `/etc/passwd` file on all nodes to identify a user ID that is available on every node. You must then specify that ID for the user on all of the nodes.

4. Set the password of the user.

For example:

```
# passwd grid
```

5. Complete user environment configuration tasks for each user.

Example of Creating Minimal Groups, Users, and Paths

You can create a minimal operating system authentication configuration as described in this example.

This configuration example shows the following:

- Creation of the Oracle Inventory group (`oinstall`)
- Creation of a single group (`dba`) as the only system privileges group to assign for all Oracle Grid Infrastructure, Oracle ASM, and Oracle Database system privileges
- Creation of the Oracle Grid Infrastructure software owner (`grid`), and one Oracle Database owner (`oracle`) with correct group memberships
- Creation and configuration of an Oracle base path compliant with OFA structure with correct permissions

Enter the following commands to create a minimal operating system authentication configuration:

```
# groupadd -g 54421 oinstall
# groupadd -g 54422 dba
# useradd -u 54321 -g oinstall -G dba oracle
# useradd -u 54322 -g oinstall -G dba grid
# mkdir -p /u01/app/23.0.0/grid
# mkdir -p /u01/app/grid
# mkdir -p /u01/app/oracle
# chown -R grid:oinstall /u01
# chown oracle:oinstall /u01/app/oracle
# chmod -R 775 /u01/
```

After running these commands, you have the following groups and users:

- An Oracle central inventory group, or `oraInventory` group (`oinstall`). Members who have the central inventory group as their primary group, are granted the `OINSTALL` permission to write to the `oraInventory` directory.
- One system privileges group, `dba`, for Oracle Grid Infrastructure, Oracle ASM and Oracle Database system privileges. Members who have the `dba` group as their primary or secondary group are granted operating system authentication for `OSASM/SYSASM`, `OSDBA/SYSDBA`, `OSOPER/SYSOPER`, `OSBACKUPDBA/SYSBACKUP`, `OSDGDBA/SYSDG`, `OSKMDBA/SYSKM`, `OSDBA for ASM/SYSDBA for ASM`, and `OSOPER for ASM/SYSOPER for Oracle ASM` to administer Oracle Clusterware, Oracle ASM, and Oracle Database, and are granted `SYSASM` and `OSOPER` for Oracle ASM access to the Oracle ASM storage.
- An Oracle Grid Infrastructure for a cluster owner, or Grid user (`grid`), with the `oraInventory` group (`oinstall`) as its primary group, and with the `OSASM` group (`dba`) as the secondary group, with its Oracle base directory `/u01/app/grid`.

- An Oracle Database owner (`oracle`) with the `oraInventory` group (`oinstall`) as its primary group, and the OSDBA group (`dba`) as its secondary group, with its Oracle base directory `/u01/app/oracle`.
- `/u01/app` owned by `grid:oinstall` with 775 permissions before installation, and by `root` after the `root.sh` script is run during installation. This ownership and permissions enables OUI to create the Oracle Inventory directory, in the path `/u01/app/oraInventory`.
- `/u01` owned by `grid:oinstall` before installation, and by `root` after the `root.sh` script is run during installation.
- `/u01/app/23.0.0/grid` owned by `grid:oinstall` with 775 permissions. These permissions are required for installation, and are changed during the installation process.
- `/u01/app/grid` owned by `grid:oinstall` with 775 permissions. These permissions are required for installation, and are changed during the installation process.
- `/u01/app/oracle` owned by `oracle:oinstall` with 775 permissions.

 **Note:**

You can use one installation owner for both Oracle Grid Infrastructure and any other Oracle installations. However, Oracle recommends that you use separate installation owner accounts for each Oracle software installation.

Example of Creating Role-allocated Groups, Users, and Paths

Understand this example of how to create role-allocated groups and users that is compliant with an Optimal Flexible Architecture (OFA) deployment.

Purpose

This example illustrates the following scenario:

- An Oracle Grid Infrastructure installation
- Two separate Oracle Database installations planned for the cluster, `DB1` and `DB2`
- Separate installation owners for Oracle Grid Infrastructure, and for each Oracle Database
- Full role allocation of system privileges for Oracle ASM, and for each Oracle Database
- Oracle Database owner `oracle1` granted the right to start up and shut down the Oracle ASM instance

Create groups and users for a role-allocated configuration for this scenario using the following commands:

```
# groupadd -g 54321 oinstall
# groupadd -g 54322 dba1
# groupadd -g 54332 dba2
# groupadd -g 54323 oper1
# groupadd -g 54333 oper2
# groupadd -g 54324 backupdba1
# groupadd -g 54334 backupdba2
# groupadd -g 54325 dgdba1
# groupadd -g 54335 dgdba2
# groupadd -g 54326 kmdba1
```

```
# groupadd -g 54336 kmdba2
# groupadd -g 54327 asmdba
# groupadd -g 54328 asmoper
# groupadd -g 54329 asmadmin
# groupadd -g 54330 racdba1
# groupadd -g 54340 racdba2
# useradd -u 54322 -g oinstall -G asmadmin,asmdba,asmoper,racdba1,racdba2 grid
# useradd -u 54321 -g oinstall -G
dba1,backupdba1,dgdba1,kmdba1,asmdba,racdba1,asmoper oracle1
# useradd -u 54323 -g oinstall -G
dba2,backupdba2,dgdba2,kmdba2,asmdba,racdba2 oracle2
# mkdir -p /u01/app/23.0.0/grid
# mkdir -p /u01/app/grid
# mkdir -p /u01/app/oracle1
# mkdir -p /u01/app/oracle2
# chown -R grid:oinstall /u01
# chmod -R 775 /u01/
# chown oracle1:oinstall /u01/app/oracle1
# chown oracle2:oinstall /u01/app/oracle2
```

After running these commands, you have a set of administrative privileges groups and users for Oracle Grid Infrastructure, and for two separate Oracle databases (DB1 and DB2):

Example 6-1 Oracle Grid Infrastructure Groups and Users Example

The command creates the following Oracle Grid Infrastructure groups and users:

- An Oracle central inventory group, or `oraInventory` group (`oinstall`), whose members that have this group as their primary group. Members of this group are granted the `OINSTALL` system privileges, which grants permissions to write to the `oraInventory` directory, and other associated install binary privileges.
- An OSASM group (`asmadmin`), associated with Oracle Grid Infrastructure during installation, whose members are granted the `SYSASM` privileges to administer Oracle ASM.
- An OSDBA for ASM group (`asmdba`), associated with Oracle Grid Infrastructure storage during installation. Its members include `grid` and any database installation owners, such as `oracle1` and `oracle2`, who are granted access to Oracle ASM. Any additional installation owners that use Oracle ASM for storage must also be made members of this group.
- An OSOPER for ASM group for Oracle ASM (`asmoper`), associated with Oracle Grid Infrastructure during installation. Members of `asmoper` group are granted limited Oracle ASM administrator privileges, including the permissions to start and stop the Oracle ASM instance.
- An OSRAC for Oracle RAC administration group (`racdba1` and `racdba2`), associated with Oracle Grid Infrastructure during installation. Members of `racdba1` and `racdba2` groups are granted limited Oracle RAC administrator privileges.
- An Oracle Grid Infrastructure installation owner (`grid`), with the `oraInventory` group (`oinstall`) as its primary group, and with the OSASM (`asmadmin`) group and the OSDBA for ASM (`asmdba`) group as secondary groups.
- `/u01/app/oraInventory`. The central inventory of Oracle installations on the cluster. This path remains owned by `grid:oinstall`, to enable other Oracle software owners to write to the central inventory.

- An OFA-compliant mount point `/u01` owned by `grid:oinstall` before installation, so that Oracle Universal Installer can write to that path.
- An Oracle base for the grid installation owner `/u01/app/grid` owned by `grid:oinstall` with 775 permissions, and changed during the installation process to 755 permissions.
- A Grid home `/u01/app/23.0.0/grid` owned by `grid:oinstall` with 775 (`drwxdrwxr-x`) permissions. These permissions are required for installation, and are changed during the installation process to `root:oinstall` with 755 permissions (`drwxr-xr-x`).

Example 6-2 Oracle Database DB1 Groups and Users Example

The command creates the following Oracle Database (DB1) groups and users:

- An Oracle Database software owner (`oracle1`), which owns the Oracle Database binaries for DB1. The `oracle1` user has the `oraInventory` group as its primary group, and the OSDBA group for its database (`dba1`) and the OSDBA for ASM group for Oracle Grid Infrastructure (`asmdba`) as secondary groups. In addition, the `oracle1` user is a member of `asmoper`, granting that user privileges to start up and shut down Oracle ASM.
- An OSDBA group (`dba1`). During installation, you identify the group `dba1` as the OSDBA group for the database installed by the user `oracle1`. Members of `dba1` are granted the SYSDBA privileges for the Oracle Database DB1. Users who connect as SYSDBA are identified as user SYS on DB1.
- An OSBACKUPDBA group (`backupdba1`). During installation, you identify the group `backupdba1` as the OSDBA group for the database installed by the user `oracle1`. Members of `backupdba1` are granted the SYSBACKUP privileges for the database installed by the user `oracle1` to back up the database.
- An OSDGDBA group (`dgdba1`). During installation, you identify the group `dgdba1` as the OSDGDBA group for the database installed by the user `oracle1`. Members of `dgdba1` are granted the SYSDG privileges to administer Oracle Data Guard for the database installed by the user `oracle1`.
- An OSKMDBA group (`kmdba1`). During installation, you identify the group `kmdba1` as the OSKMDBA group for the database installed by the user `oracle1`. Members of `kmdba1` are granted the SYSKM privileges to administer encryption keys for the database installed by the user `oracle1`.
- An OSOPER group (`oper1`). During installation, you identify the group `oper1` as the OSOPER group for the database installed by the user `oracle1`. Members of `oper1` are granted the SYSOPER privileges (a limited set of the SYSDBA privileges), including the right to start up and shut down the DB1 database. Users who connect as OSOPER privileges are identified as user PUBLIC on DB1.
- An OSRAC for Oracle RAC administration group (`racdba1`). During installation, you identify the group `racdba1` as the OSRACDBA for the database installed by the user `oracle1`. Members of `racdba1` group are granted limited Oracle RAC administrator privileges (the SYSRAC privilege).
- An Oracle base `/u01/app/oracle1` owned by `oracle1:oinstall` with 775 permissions. The user `oracle1` has permissions to install software in this directory, but in no other directory in the `/u01/app` path.

Example 6-3 Oracle Database DB2 Groups and Users Example

The command creates the following Oracle Database (DB2) groups and users:

- An Oracle Database software owner (`oracle2`), which owns the Oracle Database binaries for DB2. The `oracle2` user has the `oraInventory` group as its primary group, and the

OSDBA group for its database (`dba2`) and the OSDBA for ASM group for Oracle Grid Infrastructure (`asmdba`) as secondary groups. However, the `oracle2` user is not a member of the `asmoper` group, so `oracle2` cannot shut down or start up Oracle ASM.

- An OSDBA group (`dba2`). During installation, you identify the group `dba2` as the OSDBA group for the database installed by the user `oracle2`. Members of `dba2` are granted the SYSDBA privileges for the Oracle Database DB2. Users who connect as SYSDBA are identified as user SYS on DB2.
- An OSBACKUPDBA group (`backupdba2`). During installation, you identify the group `backupdba2` as the OSDBA group for the database installed by the user `oracle2`. Members of `backupdba2` are granted the SYSBACKUP privileges for the database installed by the user `oracle2` to back up the database.
- An OSDGDBA group (`dgdba2`). During installation, you identify the group `dgdba2` as the OSDGDBA group for the database installed by the user `oracle2`. Members of `dgdba2` are granted the SYSDG privileges to administer Oracle Data Guard for the database installed by the user `oracle2`.
- An OSKMDBA group (`kmdba2`). During installation, you identify the group `kmdba2` as the OSKMDBA group for the database installed by the user `oracle2`. Members of `kmdba2` are granted the SYSKM privileges to administer encryption keys for the database installed by the user `oracle2`.
- An OSOPER group (`oper2`). During installation, you identify the group `oper2` as the OSOPER group for the database installed by the user `oracle2`. Members of `oper2` are granted the SYSOPER privileges (a limited set of the SYSDBA privileges), including the right to start up and shut down the DB2 database. Users who connect as OSOPER privileges are identified as user PUBLIC on DB2.
- An OSRAC for Oracle RAC administration group (`racdba2`). During installation, you identify the group `racdba2` as the OSRACDBA for the database installed by the user `oracle2`. Members of `racdba2` group are granted limited Oracle RAC administrator privileges (the SYSRAC privilege).
- An Oracle base `/u01/app/oracle2` owned by `oracle2:oinstall` with 775 permissions. The user `oracle2` has permissions to install software in this directory, but in no other directory in the `/u01/app` path.

Configuring Grid Infrastructure Software Owner User Environments

Understand the software owner user environments to configure before installing Oracle Grid Infrastructure.

You run the installer software with the Oracle Grid Infrastructure installation owner user account (`oracle` or `grid`). However, before you start the installer, you must configure the environment of the installation owner user account. If needed, you must also create other required Oracle software owners.

- [Environment Requirements for Oracle Software Owners](#)
Review these requirements for Oracle software owner environments.
- [Procedure for Configuring Oracle Software Owner Environments](#)
Configure each Oracle installation owner user account environment:

- [Checking Resource Limits for Oracle Software Installation Users](#)
For each installation software owner user account, check the resource limits for installation.
- [Setting Remote Display and X11 Forwarding Configuration](#)
If you are on a remote terminal, and the local system has only one visual (which is typical), then use the following syntax to set your user account `DISPLAY` environment variable:
- [Preventing Installation Errors Caused by Terminal Output Commands](#)
During an Oracle Grid Infrastructure installation, OUI uses SSH to run commands and copy files to the other nodes. During the installation, hidden files on the system (for example, `.bashrc` or `.cshrc`) can cause `makefile` and other installation errors if they contain terminal output commands.

Environment Requirements for Oracle Software Owners

Review these requirements for Oracle software owner environments.

You must make the following changes to configure Oracle software owner environments:

- Set the installation software owner user (`grid`, `oracle`) default file mode creation mask (`umask`) to 022 in the shell startup file. Setting the mask to 022 ensures that the user performing the software installation creates files with 644 permissions.
- Set `ulimit` settings for file descriptors and processes for the installation software owner (`grid`, `oracle`).
- Set the `DISPLAY` environment variable in preparation for running an Oracle Universal Installer (OUI) installation.

Caution:

If you have existing Oracle installations that you installed with the user ID that is your Oracle Grid Infrastructure software owner, then unset all Oracle environment variable settings for that user.

Procedure for Configuring Oracle Software Owner Environments

Configure each Oracle installation owner user account environment:

1. Start an X terminal session (`xterm`) on the server where you are running the installation.
2. Enter the following command to ensure that X Window applications can display on this system, where `hostname` is the fully qualified name of the local host from which you are accessing the server:

```
$ xhost + hostname
```

3. If you are not logged in as the software owner user, then switch to the software owner user you are configuring. For example, with the user `grid`:

```
$ su - grid
```

On systems where you cannot run `su` commands, use `sudo` instead:

```
$ sudo -u grid -s
```

4. To determine the default shell for the user, enter the following command:

```
$ echo $SHELL
```

5. Open the user's shell startup file in any text editor:

- Bash shell (`bash`):

```
$ vi .bash_profile
```

- Bourne shell (`sh`) or Korn shell (`ksh`):

```
$ vi .profile
```

- C shell (`csh` or `tcsh`):

```
% vi .login
```

6. Enter or edit the following line, specifying a value of `022` for the default file mode creation mask:

```
umask 022
```

7. If the `ORACLE_SID`, `ORACLE_HOME`, or `ORACLE_BASE` environment variables are set in the file, then remove these lines from the file.

8. Save the file, and exit from the text editor.

9. To run the shell startup script, enter one of the following commands:

- Bash shell:

```
$ . ~/.bash_profile
```

- Bourne, Bash, or Korn shell:

```
$ . ~/.profile
```

- C shell:

```
% source ~/.login
```

10. Use the following command to check the `PATH` environment variable:

```
$ echo $PATH
```

Remove any Oracle environment variables.

11. Unset any Oracle environment variables.

If you have an existing Oracle software installation, and you are using the same user to install this installation, then unset the `$ORACLE_HOME`, `$ORA_NLS10`, and `$TNS_ADMIN` environment variables.

If you have set `$ORA_CRS_HOME` as an environment variable, then unset it before starting an installation or upgrade. Do not use `$ORA_CRS_HOME` as a user environment variable, except as directed by Oracle Support.

12. If you are not installing the software on the local system, then enter a command similar to the following to direct X applications to display on the local system:

- Bourne, Bash, or Korn shell:

```
$ export DISPLAY=local_host:0.0
```

- C shell:

```
% setenv DISPLAY local_host:0.0
```

In this example, `local_host` is the host name or IP address of the system (your workstation, or another client) on which you want to display the installer.

13. If the `/tmp` directory has less than 1 GB of free space, then identify a file system with at least 1 GB of free space and set the `TMP` and `TMPDIR` environment variables to specify a temporary directory on this file system:

 **Note:**

You cannot use a shared file system as the location of the temporary file directory (typically `/tmp`) for Oracle RAC installations. If you place `/tmp` on a shared file system, then the installation fails.

- a. Use the `df -h` command to identify a suitable file system with sufficient free space.
- b. If necessary, enter commands similar to the following to create a temporary directory on the file system that you identified, and set the appropriate permissions on the directory:

```
$ sudo -s
# mkdir /mount_point/tmp
# chmod 775 /mount_point/tmp
# exit
```

- c. Enter commands similar to the following to set the `TMP` and `TMPDIR` environment variables:

Bourne, Bash, or Korn shell:

```
$ TMP=/mount_point/tmp
$ TMPDIR=/mount_point/tmp
$ export TMP TMPDIR
```

C shell:

```
% setenv TMP /mount_point/tmp
% setenv TMPDIR /mount_point/tmp
```

14. To verify that the environment has been set correctly, enter the following commands:

```
$ umask
$ env | more
```

Verify that the `umask` command displays a value of `22`, `022`, or `0022` and that the environment variables you set in this section have the correct values.

Checking Resource Limits for Oracle Software Installation Users

For each installation software owner user account, check the resource limits for installation.

On Oracle Linux systems, Oracle recommends that you install Oracle Database Preinstallation RPMs to meet preinstallation requirements like configuring your operating system to set the resource limits in the `limits.conf` file.

Use the following ranges as guidelines for resource allocation to Oracle software installation owners for standard installations and to Oracle Grid Infrastructure software installation owners for job role separation:

Table 6-1 Oracle Software Installation Owner and Oracle Grid Infrastructure Software Installation Owner Resource Limit Recommended Ranges

Resource Shell Limit	Resource	Soft Limit	Hard Limit
Open file descriptors	<code>nofile</code>	at least 1024	at least 65536
Number of processes available to a single user	<code>nproc</code>	at least 2047	at least 16384
Size of the stack segment of the process	<code>stack</code>	at least 10240 KB	at least 10240 KB, and at most 32768 KB
Maximum locked memory limit	<code>memlock</code>	unlimited	unlimited

To check resource limits:

1. Log in as an installation owner.
2. Check the soft and hard limits for the file descriptor setting. Ensure that the result is in the recommended range. For example:

```
$ ulimit -Sn
1024
$ ulimit -Hn
65536
```

3. Check the soft and hard limits for the number of processes available to a user. Ensure that the result is in the recommended range. For example:

```
$ ulimit -Su
2047
$ ulimit -Hu
16384
```

4. Check the soft limit for the stack setting. Ensure that the result is in the recommended range. For example:

```
$ ulimit -Ss
10240
$ ulimit -Hs
32768
```

5. Repeat this procedure for each Oracle software installation owner.

If necessary, update the resource limits in the `/etc/security/limits.conf` configuration file for the installation owner. However, the configuration file may be distribution specific. Contact your system administrator for distribution specific configuration file information.

 **Note:**

If you make changes to an Oracle installation user account and that user account is logged in, then changes to the `limits.conf` file do not take effect until you log these users out and log them back in. You must do this before you use these accounts for installation.

Setting Remote Display and X11 Forwarding Configuration

If you are on a remote terminal, and the local system has only one visual (which is typical), then use the following syntax to set your user account `DISPLAY` environment variable:

Remote Display

Bourne, Korn, and Bash shells

```
$ export DISPLAY=hostname:0
```

C shell

```
% setenv DISPLAY hostname:0
```

For example, if you are using the Bash shell and if your host name is `local_host`, then enter the following command:

```
$ export DISPLAY=node1:0
```

X11 Forwarding

To ensure that X11 forwarding does not cause the installation to fail, use the following procedure to create a user-level SSH client configuration file for Oracle installation owner user accounts:

1. Using any text editor, edit or create the software installation owner's `~/.ssh/config` file.

2. Ensure that the `ForwardX11` attribute in the `~/.ssh/config` file is set to `no`. For example:

```
Host *
    ForwardX11 no
```

3. Ensure that the permissions on `~/.ssh` are secured to the Oracle installation owner user account. For example:

```
$ ls -al .ssh
total 28
drwx-----  2 grid oinstall 4096 Jun 21 2020
drwx----- 19 grid oinstall 4096 Jun 21 2020
-rw-r--r--  1 grid oinstall 1202 Jun 21 2020 authorized_keys
-rwx-----  1 grid oinstall  668 Jun 21 2020 id_dsa
-rwx-----  1 grid oinstall  601 Jun 21 2020 id_dsa.pub
-rwx-----  1 grid oinstall 1610 Jun 21 2020 known_hosts
```

Preventing Installation Errors Caused by Terminal Output Commands

During an Oracle Grid Infrastructure installation, OUI uses SSH to run commands and copy files to the other nodes. During the installation, hidden files on the system (for example, `.bashrc` or `.cshrc`) can cause `makefile` and other installation errors if they contain terminal output commands.

To avoid this problem, you must modify hidden files in each Oracle installation owner user home directory to suppress all output on `STDOUT` or `STDERR` (for example, `stty`, `xtitle`, and other such commands) as in the following examples:

Bourne, Bash, or Korn shell:

```
if [ -t 0 ]; then
    stty intr ^C
fi
```

C shell:

```
test -t 0
if ($status == 0) then
    stty intr ^C
endif
```

Note:

If the remote shell can load hidden files that contain `stty` commands, then OUI indicates an error and stops the installation.

Enabling Intelligent Platform Management Interface (IPMI)

Intelligent Platform Management Interface (IPMI) provides a set of common interfaces to computer hardware and firmware that system administrators can use to monitor system health and manage the system.

Oracle Clusterware can integrate IPMI to provide failure isolation support and to ensure cluster integrity. You can configure node-termination with IPMI during installation by selecting IPMI from the Failure Isolation Support screen. You can also configure IPMI after installation with `crsctl` commands.

- [Requirements for Enabling IPMI](#)
You must have the following hardware and software configured to enable cluster nodes to be managed with IPMI:
- [Configuring the IPMI Management Network](#)
You can configure the BMC for DHCP, or for static IP addresses. Oracle recommends that you configure the BMC for dynamic IP address assignment using DHCP. To use this option, you must have a DHCP server configured to assign the BMC IP addresses.
- [Configuring the Open IPMI Driver](#)
On Linux systems, the OpenIPMI driver is the supported driver for Oracle Clusterware deployments with IPMI. You can install and configure the driver dynamically by manually loading the required modules.
- [Configuring the BMC](#)
Configure BMC on each node for remote control using LAN for IPMI-based node fencing to function properly.
- [Configuring BMC Using IPMITool](#)
The following is an example of configuring BMC using `ipmitool` (version 1.8.6).

Related Topics

- *Oracle Clusterware Administration and Deployment Guide*

Requirements for Enabling IPMI

You must have the following hardware and software configured to enable cluster nodes to be managed with IPMI:

- Each cluster member node requires a Baseboard Management Controller (BMC) running firmware compatible with IPMI version 1.5 or later, which supports IPMI over LANs, and configured for remote control using LAN.
- Each cluster member node requires `ipmitool` or `ipmiutil` installed to support IPMI version 2.0 or later.
- The cluster requires a management network for IPMI. This can be a shared network, but Oracle recommends that you configure a dedicated network.
- Each cluster member node's port used by BMC must be connected to the IPMI management network.
- Each cluster member must be connected to the management network.
- Some server platforms put their network interfaces into a power saving mode when they are powered off. In this case, they may operate only at a lower link speed (for example, 100 MB, instead of 1 GB). For these platforms, the network switch port to which the BMC is connected must be able to auto-negotiate down to the lower speed, or IPMI will not function properly.

 **Note:**

IPMI operates on the physical hardware platform through the network interface of the baseboard management controller (BMC). Depending on your system configuration, an IPMI-initiated restart of a server can affect all virtual environments hosted on the server. Contact your hardware and OS vendor for more information.

Configuring the IPMI Management Network

You can configure the BMC for DHCP, or for static IP addresses. Oracle recommends that you configure the BMC for dynamic IP address assignment using DHCP. To use this option, you must have a DHCP server configured to assign the BMC IP addresses.

For Oracle Clusterware to communicate with the BMC, the IPMI driver must be installed permanently on each node, so that it is available on system restarts. The IPMI driver is available on the Asianux Linux, Oracle Linux, Red Hat Enterprise Linux, and SUSE Linux Enterprise Server distributions supported with this release.

 **Note:**

If you configure IPMI, and you use Grid Naming Service (GNS) you still must configure separate addresses for the IPMI interfaces. As the IPMI adapter is not seen directly by the host, the IPMI adapter is not visible to GNS as an address on the host.

Configuring the Open IPMI Driver

On Linux systems, the OpenIPMI driver is the supported driver for Oracle Clusterware deployments with IPMI. You can install and configure the driver dynamically by manually loading the required modules.

 **Note:**

You must configure the IPMI driver either on all or none of the cluster nodes.

Contact your Linux distribution vendor for information about how to configure IPMI for your distribution. Configure the Open IPMI driver manually on Oracle Linux as follows:

1. Log in as `root`.
2. Run the following commands:

```
# /sbin/modprobe ipmi_msghandler
# /sbin/modprobe ipmi_si
# /sbin/modprobe ipmi_devintf
```

3. (Optional) Run the command `/sbin/lsmmod |grep ipmi` to confirm that the IPMI modules are loaded. For example:

```
# /sbin/lsmmod | grep ipmi
ipmi_devintf 12617 0
```



```
ipmi_si 33377 0
ipmi_msghandler 33701 2
ipmi_devintf,ipmi_si
```

You can install the modules whether or not a BMC is present.

4. Open the `/etc/rc.local` file using a text editor, navigate to the end of the file, and enter lines similar to the following, to run the `modprobe` commands in step 2 automatically on system restart:

```
# START IPMI ON SYSTEM RESTART
/sbin/modprobe ipmi_msghandler
/sbin/modprobe ipmi_si
/sbin/modprobe ipmi_devintf
```

On SUSE Linux Enterprise Server systems, add the `modprobe` commands above to `/etc/init.d/boot.local`.

5. Check to ensure that the Linux system is recognizing the IPMI device, using the following command:

```
ls -l /dev/ipmi0
```

If the IPMI device is dynamically loaded, then the output must be similar to the following:

```
# ls -l /dev/ipmi0 crw----- 1 root root 253, 0 Sep 23 06:29 /dev/ipmi0
```

If you do see the device file output, then the IPMI driver is configured, and you can ignore the following step.

If you do not see the device file output, then the `udev` daemon is not set up to create device files automatically. Proceed to the next step.

6. Determine the device major number for the IPMI device using the command `grep ipmi /proc/devices`. For example:

```
# grep ipmi /proc/devices 253 ipmidev
```

The device major number is 253.

7. Run the `mknod` command to create a directory entry and `i-node` for the IPMI device, using the device major number. For example:

```
# mknod /dev/ipmi0 c 253 0x0
```

The permissions on `/dev/ipmi0` in the example allow the device to be accessible only by root. The device should only be accessed by root, to prevent a system vulnerability.

Configuring the BMC

Configure BMC on each node for remote control using LAN for IPMI-based node fencing to function properly.

You can configure BMC from the BIOS prompt, using a distribution-specific management utility, or you can configure BMC using publicly available utilities, such as the following: IPMITool, which is available for Linux:

<http://ipmitool.sourceforge.net>

IPMIutil, which is available for Linux:

<http://ipmiutil.sourceforge.net>

Refer to the documentation for the configuration tool you select for details about using the tool to configure the BMC.

When you configure the BMC on each node, you must complete the following:

1. Enable IPMI over LAN, so that the BMC can be controlled over the management network.
2. Enable dynamic IP addressing using DHCP or GNS, or configure a static IP address for the BMC.
3. Establish an administrator user account and password for the BMC.
4. Configure the BMC for VLAN tags, if you will use the BMC on a tagged VLAN.

The configuration tool you use does not matter, but these conditions must be met for the BMC to function properly.

Configuring BMC Using IPMITool

The following is an example of configuring BMC using `ipmitool` (version 1.8.6).

1. Log in as `root`.
2. Verify that `ipmitool` can communicate with the BMC using the IPMI driver by using the command `bmc info`, and looking for a device ID in the output. For example:

```
# ipmitool bmc info
Device ID           : 32
.
.
.
```

If `ipmitool` is not communicating with the BMC, then review the section *Configuring the BMC* and ensure that the IPMI driver is running.

3. Enable IPMI over LAN using the following procedure:
 - a. Determine the channel number for the channel used for IPMI over LAN. Beginning with channel 1, run the following command until you find the channel that displays LAN attributes (for example, the IP address):

```
# ipmitool lan print 1
. . .
IP Address Source   : 0x01
```

```
IP Address           : 140.87.155.89
. . .
```

- b. Turn on LAN access for the channel found. For example, where the channel is 1:

```
# ipmitool -I bmc lan set 1 access on
```

4. Configure IP address settings for IPMI using the static IP addressing procedure:

If the BMC shares a network connection with ILOM, then the IP address must be on the same subnet. You must set not only the IP address, but also the proper values for netmask, and the default gateway. For example, assuming the channel is 1:

```
# ipmitool -I bmc lan set 1 ipaddr 192.168.0.55
# ipmitool -I bmc lan set 1 netmask 255.255.255.0
# ipmitool -I bmc lan set 1 defgw ipaddr 192.168.0.1
```

Note that the specified address (192.168.0.55) is associated only with the BMC, and does not respond to normal pings.

5. Establish an administration account with a username and password, using the following procedure (assuming the channel is 1):

- a. Set BMC to require password authentication for ADMIN access over LAN. For example:

```
# ipmitool -I bmc lan set 1 auth ADMIN MD5,PASSWORD
```

- b. List the account slots on the BMC, and identify an unused slot less than the maximum ID and not listed, for example, ID 4 in the following example. Note that some slots may be reserved and not available for reuse on some hardware.

```
# ipmitool user summary 1
Maximum IDs           : 20
Enabled User Count    : 3
Fixed Name Count      : 2
# ipmitool user list 1
ID Name      Enabled Callin Link Auth IPMI Msg Channel Priv Lim
1           true   false  false   true   USER
2  root      true   false  false   true   ADMINISTRATOR
3  sysoper   true   true   false   true   OPERATOR
12 default   true   true   false   true   NO ACCESS
13           true   false  true    false  CALLBACK
```

In the example above, there are 20 possible slots, and the first unused slot is number 4.

- c. Assign the desired administrator user name and password and enable messaging for the identified slot. (Note that for IPMI v1.5 the user name and password can be at most 16 characters). Also, set the privilege level for that slot when accessed over LAN (channel 1) to ADMIN (level 4). For example, where *username* is the administrative user name, and *password* is the password:

```
# ipmitool user set name 4 username
# ipmitool user set password 4 password
```

```
# ipmitool user enable 4
# ipmitool channel setaccess 1 4 privilege=4
# ipmitool channel setaccess 1 4 link=on
# ipmitool channel setaccess 1 4 ipmi=on
```

- d. Verify the setup using the command `lan print 1`. The output should appear similar to the following. Note that the items in **bold** text are the settings made in the preceding configuration steps, and comments or alternative options are indicated within brackets []:

```
# ipmitool lan print 1
Set in Progress          : Set Complete
Auth Type Support       : NONE MD2 MD5 PASSWORD
Auth Type Enable        : Callback : MD2 MD5
                        : User      : MD2 MD5
                        : Operator : MD2 MD5
                        : Admin   : MD5 PASSWORD
                        : OEM      : MD2 MD5

IP Address Source      : DHCP Address [or Static Address]
IP Address           : 192.168.0.55
Subnet Mask         : 255.255.255.0
MAC Address             : 00:14:22:23:fa:f9
SNMP Community String   : public
IP Header               : TTL=0x40 Flags=0x40 Precedence=...
Default Gateway IP   : 192.168.0.1
Default Gateway MAC     : 00:00:00:00:00:00
.
.
.
# ipmitool channel getaccess 1 4
Maximum User IDs        : 10
Enabled User IDs        : 2

User ID                 : 4
User Name           : username [This is the administration user]
Fixed Name              : No
Access Available        : call-in / callback
Link Authentication : enabled
IPMI Messaging     : enabled
Privilege Level     : ADMINISTRATOR
```

6. Verify that the BMC is accessible and controllable from a remote node in your cluster using the `bmc info` command. For example, if `node2-ipmi` is the network host name assigned the IP address of `node2`'s BMC, then to verify the BMC on `node2` from `node1`, with the administrator account `username`, enter the following command on `node1`:

```
$ ipmitool -H node2-ipmi -U username lan print 1
```

You are prompted for a password. Provide the IPMI password.

If the BMC is correctly configured, then you should see information about the BMC on the remote node. If you see an error message, such as `Error: Unable to establish LAN session`, then you must check the BMC configuration on the remote node.

7. Repeat this process for each cluster member node. If the IPMI administrator account credentials on each cluster member node are not identical, then IPMI will fail during configuration.

7

Supported Storage Options for Oracle Database and Oracle Grid Infrastructure

Review supported storage options as part of your installation planning process.

- [Supported Storage Options for Oracle Grid Infrastructure](#)
The following table shows the storage options supported for Oracle Grid Infrastructure binaries and files:
- [Oracle ACFS and Oracle ADVM](#)
Oracle Advanced Cluster File System (Oracle ACFS) extends Oracle ASM technology to support of all of your application data in both single instance and cluster configurations.
- [Storage Considerations for Oracle Grid Infrastructure and Oracle RAC](#)
For all installations, you must choose the storage option to use for Oracle Grid Infrastructure (Oracle Clusterware and Oracle ASM), and Oracle Real Application Clusters (Oracle RAC) databases.
- [Guidelines for Using Oracle ASM Disk Groups for Storage](#)
Plan how you want to configure Oracle ASM disk groups for deployment.
- [Guidelines for Configuring Oracle ASM Disk Groups on NFS](#)
Configuration guidelines for Automatic Storage Management (Oracle ASM) on NFS file systems.
- [Using Logical Volume Managers with Oracle Grid Infrastructure and Oracle RAC](#)
Oracle Grid Infrastructure and Oracle RAC only support cluster-aware volume managers.
- [Using a Cluster File System for Oracle Clusterware Files](#)
Starting with Oracle Grid Infrastructure 19c, you can use Oracle Automatic Storage Management (Oracle ASM) or certified shared file system to store OCR files and voting files.
- [About NFS Storage for Data Files](#)
Review this section for NFS storage configuration guidelines.
- [About Direct NFS Client Mounts to NFS Storage Devices](#)
Direct NFS Client integrates the NFS client functionality directly in the Oracle software to optimize the I/O path between Oracle and the NFS server. This integration can provide significant performance improvements.

Supported Storage Options for Oracle Grid Infrastructure

The following table shows the storage options supported for Oracle Grid Infrastructure binaries and files:

Table 7-1 Supported Storage Options for Oracle Grid Infrastructure

Storage Option	OCR and Voting Files	Oracle Clusterware Binaries	Oracle RAC Database Binaries	Oracle RAC Database Data Files	Oracle RAC Database Recovery Files
Oracle Automatic Storage Management (Oracle ASM) Note: Loopback devices are not supported for use with Oracle ASM	Yes	No	No	Yes	Yes
Oracle Advanced Cluster File System (Oracle ACFS)	No	No	Yes	Yes	Yes
NVMe over Fabrics (NVMe-oF) storage devices	No	No	No	Yes	Yes
Local file system	No	Yes	Yes	No	No
OCFS2	No	No	Yes	Yes	Yes
Network file system (NFS) on a certified network-attached storage (NAS) filer Note: Direct NFS Client does not support Oracle Clusterware files	Yes	Yes	Yes	Yes	Yes
Direct-attached storage (DAS)	No	No	Yes	Yes	Yes
Shared disk partitions (block devices or raw devices)	No	No	No	No	No

Guidelines for Storage Options

Use the following guidelines when choosing storage options:

- You can choose any combination of the supported storage options for each file type provided that you satisfy all requirements listed for the chosen storage options.

- You can use Oracle ASM or shared file system to store Oracle Clusterware files.
- Direct use of raw or block devices is not supported.

Related Topics

- *Oracle Database Upgrade Guide*

Oracle ACFS and Oracle ADVM

Oracle Advanced Cluster File System (Oracle ACFS) extends Oracle ASM technology to support of all of your application data in both single instance and cluster configurations.

Oracle Automatic Storage Management Dynamic Volume Manager (Oracle ADVM) provides volume management services and a standard disk device driver interface to clients. Oracle ACFS communicates with Oracle ASM through the Oracle ADVM interface.

 **Note:**

Starting with Oracle Database 21c, the name of Oracle Automatic Storage Management Cluster File System (Oracle ACFS) is changed to Oracle Advanced Cluster File System (Oracle ACFS).

This change is only a change of the name. The basic function of Oracle's cluster file system continues to be the same. Oracle continues to develop and enhance Oracle ACFS.

- [Oracle ACFS and Oracle ADVM Support on Linux x86–64](#)
Oracle ACFS and Oracle ADVM are supported on Oracle Linux, Red Hat Enterprise Linux, and SUSE Linux Enterprise Server.
- [Restrictions and Guidelines for Oracle ACFS](#)
Review these topics as part of your storage plan for using Oracle ACFS for single instance and cluster configurations.

Related Topics

- *Oracle Advanced Cluster File System Administrator's Guide*

Oracle ACFS and Oracle ADVM Support on Linux x86–64

Oracle ACFS and Oracle ADVM are supported on Oracle Linux, Red Hat Enterprise Linux, and SUSE Linux Enterprise Server.

Table 7-2 Platforms That Support Oracle ACFS and Oracle ADVM

Platform / Operating System	Kernel
Oracle Linux 9	All Oracle Linux 9.3 Unbreakable Enterprise Linux (UEK) kernels; Red Hat Compatible Kernel (RHCK) 9.3 and later kernels.
Oracle Linux 8	All Oracle Linux 8.8 Unbreakable Enterprise Linux (UEK) kernels; Red Hat Compatible Kernel (RHCK) 8.8 and later kernels.
Red Hat Enterprise Linux 9.2	Red Hat Enterprise Linux 9.2 and later kernels.
Red Hat Enterprise Linux 8.8	Red Hat Enterprise Linux 8.8 and later kernels.
SUSE Linux Enterprise Server 15	SUSE Linux Enterprise Server 15 SP5 and later kernels

Table 7-2 (Cont.) Platforms That Support Oracle ACFS and Oracle ADVM

Platform / Operating System	Kernel
Linux Containers	Not supported

Note:

If you use Security Enhanced Linux (SELinux) in enforcing mode with Oracle ACFS, then ensure that you mount the Oracle ACFS file systems with an SELinux default context. Refer to your Linux vendor documentation for information about the context mount option.

Important:

You must apply patches to some of the Linux kernel versions for successful Oracle Grid Infrastructure installation. Refer to the following notes for more information:

- My Oracle Support Note 1369107.1 for more information and a complete list of platforms and releases that support Oracle ACFS and Oracle ADVM:

<https://support.oracle.com/rs?type=doc&id=1369107.1>

- Patch Set Updates for Oracle Products (My Oracle Support Note 854428.1) for current release and support information:

<https://support.oracle.com/rs?type=doc&id=854428.1>

Restrictions and Guidelines for Oracle ACFS

Review these topics as part of your storage plan for using Oracle ACFS for single instance and cluster configurations.

ACFS Restrictions for Oracle Database and Oracle Grid Infrastructure

Oracle Advanced Cluster File System (Oracle ACFS) provides a general purpose file system. You can only use Oracle ACFS when Oracle ASM is configured.

Note the following general guidelines and restrictions for placing Oracle Database and Oracle Grid Infrastructure files on Oracle ACFS:

- You can place Oracle Database binaries, data files, and administrative files (for example, trace files) on Oracle ACFS.
- Oracle ACFS does not support encryption or replication with Oracle Database data files, tablespace files, control files, redo logs, archive logs, RMAN backups, Data Pump dumpsets, and flashback files.
- You can place Oracle Database homes on Oracle ACFS only if the database release is Oracle Database 11g Release 2, or more recent releases. You cannot install earlier releases of Oracle Database on Oracle ACFS.
- For installations on Oracle Clusterware, you cannot place Oracle Clusterware files on Oracle ACFS.

ACFS Restrictions for Oracle Restart

Oracle Restart does not support root-based Oracle Clusterware resources. For this reason, the following restrictions apply if you run Oracle ACFS on an Oracle Restart Configuration:

- Starting with Oracle Database 18c, configuration assistants do not allow the creation of Oracle Database homes on Oracle ACFS in an Oracle Restart configuration.
- Oracle Restart does not support Oracle ACFS resources on all platforms.
- Starting with Oracle Database 12c, Oracle Restart configurations do not support the Oracle ACFS registry.
- On Linux, Oracle ACFS provides an automated mechanism to load and unload drivers and mount and unmount Oracle ACFS file systems on system restart and shutdown. However, Oracle ACFS does not provide automated recovery of mounted file systems when the system is running. Other than Linux, Oracle ACFS does not provide this automated mechanism on other operating systems.
- Creating Oracle data files on an Oracle ACFS file system is not supported in Oracle Restart configurations. Creating Oracle data files on an Oracle ACFS file system is supported on Oracle Grid Infrastructure for a cluster configurations.

Related Topics

- *Oracle Advanced Cluster File System Administrator's Guide*

Storage Considerations for Oracle Grid Infrastructure and Oracle RAC

For all installations, you must choose the storage option to use for Oracle Grid Infrastructure (Oracle Clusterware and Oracle ASM), and Oracle Real Application Clusters (Oracle RAC) databases.

Storage Considerations for Oracle Clusterware

Oracle Clusterware voting files are used to monitor cluster node status, and Oracle Cluster Registry (OCR) files contain configuration information about the cluster. You can store Oracle Cluster Registry (OCR) and voting files on Oracle ASM disk groups or a shared file system. You can also store a backup of the OCR file in a disk group. Storage must be shared; any node that does not have access to an absolute majority of voting files (more than half) is restarted.

If you use Oracle ASM disk groups created on Network File System (NFS) for storage, then ensure that you follow the recommendations for mounting NFS described in the topic *Guidelines for Configuring Oracle ASM Disk Groups on NFS*.

Storage Considerations for Oracle RAC

Oracle ASM is a supported storage option for database and recovery files. For all installations, Oracle recommends that you create at least two separate Oracle ASM disk groups: One for Oracle Database data files, and one for recovery files. Oracle recommends that you place the Oracle Database disk group and the recovery files disk group in separate failure groups.

- If you do not use Oracle ASM for database files, then Oracle recommends that you place the data files and the Fast Recovery Area in shared storage located outside of the Oracle home, in separate locations, so that a hardware failure does not affect availability.
- You can choose any combination of the supported storage options for each file type provided that you satisfy all requirements listed for the chosen storage options.

- If you plan to install an Oracle RAC home on a shared OCFS2 location, then you must upgrade OCFS2 to at least version 1.4.1, which supports shared writable memory maps.
- To use Oracle ASM with Oracle RAC, and if you are configuring a new Oracle ASM instance, then your system must meet the following conditions:
 - All nodes on the cluster have Oracle Clusterware and Oracle ASM 23ai installed as part of an Oracle Grid Infrastructure for a cluster installation.
 - Any existing Oracle ASM instance on any node in the cluster is shut down.
 - To provide voting file redundancy, one Oracle ASM disk group is sufficient. The Oracle ASM disk group provides three or five copies.

You can use NFS, with or without Direct NFS, to store Oracle Database data files.

Guidelines for Using Oracle ASM Disk Groups for Storage

Plan how you want to configure Oracle ASM disk groups for deployment.

During Oracle Grid Infrastructure installation, you can create one or two Oracle ASM disk groups. After the Oracle Grid Infrastructure installation, you can create additional disk groups using Oracle Automatic Storage Management Configuration Assistant (ASMCA), SQL*Plus, or Automatic Storage Management Command-Line Utility (ASMCMD).

Choose to create a second disk group during Oracle Grid Infrastructure installation. The first disk group stores the Oracle Cluster Registry (OCR), voting files, and the Oracle ASM password file. The second disk group stores Oracle Cluster Registry (OCR) backup files. Oracle strongly recommends that you store the OCR backup files in a different disk group from the disk group where you store OCR files. In addition, having a second disk group is advisable for performance, availability, sizing, and manageability of storage.

If you install Oracle Database or Oracle RAC after you install Oracle Grid Infrastructure, then you can either use the same disk group for database files, OCR, and voting files, or you can use different disk groups. If you create multiple disk groups before installing Oracle RAC or before creating a database, then you can do one of the following:

- Place the data files in the same disk group as the Oracle Clusterware files.
- Use the same Oracle ASM disk group for data files and recovery files.
- Use different disk groups for each file type.

If you create only one disk group for storage, then the OCR and voting files, database files, and recovery files are contained in the one disk group. If you create multiple disk groups for storage, then you can place files in different disk groups.

See Also:

Oracle Automatic Storage Management Administrator's Guide for information about creating disk groups

Guidelines for Configuring Oracle ASM Disk Groups on NFS

Configuration guidelines for Automatic Storage Management (Oracle ASM) on NFS file systems.

You can create Oracle ASM disk groups on NFS (Network File System) or block devices on a supported Network Attached Storage (NAS) device. Understand the following guidelines for configuring Oracle ASM disk groups on NFS:



Note:

All storage products must be supported by both your server and storage vendors.

Guidelines for Deploying Oracle ASM Disk Groups Without Quorum Disks

- To use an NFS file system, it must be on a supported NAS device. Log in to My Oracle Support at the following URL, and click Certifications to find the most current information about supported NAS devices:
<https://support.oracle.com/>
- NFS file systems must be mounted and available over NFS mounts before you start installation. Refer to your vendor documentation to complete NFS configuration and mounting.
- Direct NFS requires hard mounts. Hard mounting NFS filers prevents corruption which could occur if the client connection were to time out. If an NFS filer stops responding on an I/O operation to a mirrored file, then the database and Oracle ASM cannot failover to the remaining mirror copy. Therefore, Oracle recommends that you use external redundancy when you deploy Oracle ASM disk groups on NFS storage.
- Oracle ASM Filter Driver and Oracle ACFS and Oracle ADVM are not supported with NFS. These features are incompatible because of the nature of the operating system interface for NFS-based storage.



Note:

Oracle ACFS does not support NFS disks in an Oracle ASM disk group, but you can use NFS disks with Oracle ACFS using Oracle ACFS NAS Maximum Availability eXtensions (Oracle ACFS NAS MAX).

- The performance of Oracle software and databases stored on Oracle ASM disk groups on NFS depends on the performance of the network connection between the Oracle server and the NAS device. Oracle recommends that you connect the server to the NAS device using a private dedicated network connection, which should be Gigabit Ethernet or better.
- You can configure Oracle ASM on NFS when you deploy Oracle Grid Infrastructure to manage Oracle RAC databases.
- You can specify separate NFS locations for Oracle ASM disk groups for Oracle Clusterware files and OCR backup.
- The user account with which you perform the installation (`oracle` or `grid`) must have write permissions to create the files in the path that you specify.
- When you choose Oracle ASM on NFS, you cannot use Oracle Advanced Cluster File System (Oracle ACFS) for storage. This cluster configuration cannot be used as a Oracle Fleet Patching and Provisioning Server.

Guidelines for Deploying Oracle ASM Disk Groups With Quorum Disks

- SAN-attached storage or iSCSI-attached devices are the preferred ways to connect to quorum disks. If your standard deployment requires NFS to be used as storage, then use soft mounts for NFS-based Oracle ASM quorum disks and hard mounts for other Oracle ASM disks.
- You can use Direct NFS (dNFS) for storage of Oracle Database data files. dNFS does not support soft mounts, so you cannot use dNFS for quorum failure groups. Alternatively, use kernel-based NFS with a soft mount for NFS storage residing in a quorum failure group.
- The quorum failure group feature in Oracle ASM enables use of NFS storage in an Oracle ASM disk group without requiring a hard mount for NFS storage in the quorum failure group. This capability is useful for Oracle Extended Clusters where a third site is required for establishing quorum.

Related Topics

- [Creating Files on a NAS Device for Use with Oracle Automatic Storage Management](#)
If you have a certified NAS storage device, then you can create zero-padded files in an NFS mounted directory and use those files as disk devices in an Oracle ASM disk group.

Using Logical Volume Managers with Oracle Grid Infrastructure and Oracle RAC

Oracle Grid Infrastructure and Oracle RAC only support cluster-aware volume managers.

Oracle Grid Infrastructure and Oracle RAC only support cluster-aware volume managers. Some third-party volume managers are not cluster-aware, and so are not supported. To confirm that a volume manager you want to use is supported, click **Certifications** on My Oracle Support to determine if your volume manager is certified for Oracle RAC. My Oracle Support is available at the following URL:

<https://support.oracle.com>

Using a Cluster File System for Oracle Clusterware Files

Starting with Oracle Grid Infrastructure 19c, you can use Oracle Automatic Storage Management (Oracle ASM) or certified shared file system to store OCR files and voting files.

For new Oracle Grid Infrastructure installations, you can use Oracle ASM or shared file system to store voting files and OCR files. For Linux 86-64 (64-bit) platform, Oracle provides a cluster file system, OCFS2. However, Oracle does not recommend using OCFS2 for Oracle Clusterware files.

About NFS Storage for Data Files

Review this section for NFS storage configuration guidelines.

Network-Attached Storage and NFS Protocol

Network-attached storage (NAS) systems use the network file system (NFS) protocol to access files over a network, which enables client servers to access files over networks as easily as to storage devices attached directly to the servers. You can store data files on

supported NFS systems. NFS is a shared file system protocol, so NFS can support both single instance and Oracle Real Application Clusters databases.

 **Note:**

The performance of Oracle software and databases stored on NAS devices depends on the performance of the network connection between the servers and the network-attached storage devices. For better performance, Oracle recommends that you connect servers to NAS devices using private dedicated network connections. NFS network connections should use Gigabit Ethernet or better.

Refer to your vendor documentation to complete NFS configuration and mounting.

Requirements for Using NFS Storage

Before you start installation, NFS file systems must be mounted and available to servers.

About Direct NFS Client Mounts to NFS Storage Devices

Direct NFS Client integrates the NFS client functionality directly in the Oracle software to optimize the I/O path between Oracle and the NFS server. This integration can provide significant performance improvements.

Direct NFS Client supports NFSv3, NFSv4, NFSv4.1, and pNFS protocols to access the NFS server. Direct NFS Client also simplifies, and in many cases automates, the performance optimization of the NFS client configuration for database workloads.

Starting with Oracle Database 12c Release 2, when you enable Direct NFS, you can also enable the Direct NFS dispatcher. The Direct NFS dispatcher consolidates the number of TCP connections that are created from a database instance to the NFS server. In large database deployments, using Direct NFS dispatcher improves scalability and network performance. Parallel NFS deployments also require a large number of connections. Hence, the Direct NFS dispatcher is recommended with Parallel NFS deployments too.

Direct NFS Client can obtain NFS mount points either from the operating system mount entries, or from the `oranfstab` file.

Direct NFS Client Requirements

- NFS servers must have write size values (`wtmax`) of 32768 or greater to work with Direct NFS Client.
- NFS mount points must be mounted both by the operating system kernel NFS client and Direct NFS Client, even though you configure Direct NFS Client to provide file service.

If Oracle Database cannot connect to an NFS server using Direct NFS Client, then Oracle Database connects to the NFS server using the operating system kernel NFS client. When Oracle Database fails to connect to NAS storage through Direct NFS Client, it logs an informational message about the Direct NFS Client connect error in the Oracle alert and trace files.

- Follow standard guidelines for maintaining integrity of Oracle Database files mounted by both operating system NFS and by Direct NFS Client.

Direct NFS Mount Point Search Order

Direct NFS Client searches for mount entries in the following order:

1. ORACLE_BASE_HOME/dbs/oranfstab
2. ORACLE_BASE_CONFIG/dbs/oranfstab
3. /etc/oranfstab
4. /etc/mtab

Direct NFS Client uses the first matching entry as the mount point.

Note:

You can have only one active NFS Client implementation for each instance. Enabling Direct NFS Client on an instance prevents you from using another NFS Client implementation, such as kernel NFS Client.

- To print the ORACLE_BASE_HOME path, run:

```
$ setenv ORACLE_HOME /u01/app/oracle/product/23.0.0/dbhome_1
$ cd $ORACLE_HOME/bin
$ ./orabasehome
```

- To print the ORACLE_BASE_CONFIG path, run:

```
$ setenv ORACLE_HOME /u01/app/oracle/product/23.0.0/dbhome_1
$ cd $ORACLE_HOME/bin
$ ./orabaseconfig
```

See Also:

- *Oracle Database Reference* for information about setting the `enable_dnfs_dispatcher` parameter in the initialization parameter file to enable Direct NFS dispatcher
- *Oracle Database Performance Tuning Guide* for performance benefits of enabling Parallel NFS and Direct NFS dispatcher
- *Oracle Automatic Storage Management Administrator's Guide* for guidelines about managing Oracle Database data files created with Direct NFS Client or kernel NFS

8

Configuring Storage for Oracle Grid Infrastructure

Complete these procedures to configure Oracle Automatic Storage Management (Oracle ASM) for Oracle Grid Infrastructure for a cluster.

Oracle Grid Infrastructure for a cluster provides system support for Oracle Database. Oracle ASM is a volume manager and a file system for Oracle database files that supports single-instance Oracle Database and Oracle Real Application Clusters (Oracle RAC) configurations. Oracle Automatic Storage Management also supports a general purpose file system for your application needs, including Oracle Database binaries. Oracle Automatic Storage Management is Oracle's recommended storage management solution. It provides an alternative to conventional volume managers and file systems.

Note:

Oracle ASM and shared file system are the supported storage management solutions for Oracle Cluster Registry (OCR) and Oracle Clusterware voting files. The OCR is a file that contains the configuration information and status of the cluster. The installer automatically initializes the OCR during the Oracle Clusterware installation. Database Configuration Assistant uses the OCR for storing the configurations for the cluster databases that it creates.

- [Configuring Storage for Oracle Automatic Storage Management](#)
Identify storage requirements and Oracle ASM disk group options.
- [Configuring Storage Device Path Persistence Using Oracle ASMFDD](#)
Oracle ASM Filter Driver (Oracle ASMFDD) maintains storage file path persistence and helps to protect files from accidental overwrites.
- [Configuring NVMe Over Fabrics Storage Devices with Oracle ASM](#)
You can use NVMe over Fabrics storage devices with Oracle Automatic Storage Management (Oracle ASM) to create Oracle ASM disk groups.
- [Using Disk Groups with Oracle Database Files on Oracle ASM](#)
Review this information to configure Oracle Automatic Storage Management (Oracle ASM) storage for Oracle Clusterware and Oracle Database Files.
- [Configuring File System Storage for Oracle Database](#)
Complete these procedures to use file system storage for Oracle Database.
- [Creating Oracle ASM Client Data File](#)
Generate an Oracle ASM client data file and copy the file to the Oracle ASM client cluster member node on which you are installing Oracle Grid Infrastructure.
- [Configuring Oracle Advanced Cluster File System](#)
Review this information to configure Oracle ACFS for an Oracle RAC Oracle Database home.
- [Checking OCFS2 Version Manually](#)
Use the following command to check your OCFS2 version manually.

Configuring Storage for Oracle Automatic Storage Management

Identify storage requirements and Oracle ASM disk group options.

- [Identifying Storage Requirements for Oracle Automatic Storage Management](#)
To identify the storage requirements for using Oracle ASM, you must determine the number of devices and the amount of free disk space that you require.
- [Oracle Clusterware Storage Space Requirements](#)
Use this information to determine the minimum number of disks and the minimum disk space requirements based on the redundancy type, for installing Oracle Clusterware files for various Oracle Cluster deployments.
- [Using an Existing Oracle ASM Disk Group](#)
Use Oracle Enterprise Manager Cloud Control or the Oracle ASM command line tool (`asmcmd`) to identify existing disk groups, and to determine if sufficient space is available in the disk group.
- [About Upgrading Existing Oracle Automatic Storage Management Instances](#)
Oracle Automatic Storage Management (Oracle ASM) upgrades are carried out during an Oracle Grid Infrastructure upgrade.
- [Selecting Disks to use with Oracle ASM Disk Groups](#)
If you are sure that a suitable disk group does not exist on the system, then install or identify appropriate disk devices to add to a new disk group.
- [Specifying the Oracle ASM Disk Discovery String](#)
When an Oracle ASM instance is initialized, Oracle ASM discovers and examines the contents of all of the disks that are in the paths that you designated with values in the `ASM_DISKSTRING` initialization parameter.
- [Creating Files on a NAS Device for Use with Oracle Automatic Storage Management](#)
If you have a certified NAS storage device, then you can create zero-padded files in an NFS mounted directory and use those files as disk devices in an Oracle ASM disk group.

Related Topics

- *Oracle Automatic Storage Management Administrator's Guide*

Identifying Storage Requirements for Oracle Automatic Storage Management

To identify the storage requirements for using Oracle ASM, you must determine the number of devices and the amount of free disk space that you require.

To complete this task, follow these steps:

1. Plan your Oracle ASM disk groups requirement, based on the cluster configuration you want to deploy.
2. Determine whether you want to use Oracle ASM for Oracle Database files, recovery files, and Oracle Database binaries. Oracle Database files include data files, control files, redo log files, the server parameter file, and the password file.

 **Note:**

- You do not have to use the same storage mechanism for Oracle Database files and recovery files. You can use a shared file system for one file type and Oracle ASM for the other.
- There are two types of Oracle Clusterware files: OCR files and voting files. You can use either Oracle ASM or a shared file system to store OCR and voting files on Oracle Grid Infrastructure deployments.
- If your database files are stored on a shared file system, then you can continue to use the same for database files, instead of moving them to Oracle ASM storage.

3. Choose the Oracle ASM redundancy level to use for the Oracle ASM disk group.

Except when using external redundancy, Oracle ASM mirrors all Oracle Clusterware files in separate failure groups within a disk group. A quorum failure group, a special type of failure group, contains mirror copies of voting files when voting files are stored in normal or high redundancy disk groups. The disk groups that contain Oracle Clusterware files (OCR and voting files) have a higher minimum number of failure groups than other disk groups because the voting files are stored in quorum failure groups in the Oracle ASM disk group.

A quorum failure group is a special type of failure group that is used to store the Oracle Clusterware voting files. The quorum failure group is used to ensure that a quorum of the specified failure groups are available. When Oracle ASM mounts a disk group that contains Oracle Clusterware files, the quorum failure group is used to determine if the disk group can be mounted in the event of the loss of one or more failure groups. Disks in the quorum failure group do not contain user data, therefore a quorum failure group is not considered when determining redundancy requirements in respect to storing user data.

The redundancy levels are as follows:

- **High redundancy**

In a high redundancy disk group, Oracle ASM uses three-way mirroring to increase performance and provide the highest level of reliability. A high redundancy disk group requires a minimum of three disk devices (or three failure groups). The effective disk space in a high redundancy disk group is one-third the sum of the disk space in all of its devices.

For Oracle Clusterware files, a high redundancy disk group requires a minimum of five disk devices and provides five voting files and one OCR (one primary and two secondary copies). For example, your deployment may consist of three regular failure groups and two quorum failure groups. Note that not all failure groups can be quorum failure groups, even though voting files need all five disks. With high redundancy, the cluster can handle the loss of two failure groups.

While high redundancy disk groups do provide a high level of data protection, you should consider the greater cost of additional storage devices before deciding to select high redundancy disk groups.

- **Normal redundancy**

In a normal redundancy disk group, to increase performance and reliability, Oracle ASM by default uses two-way mirroring. A normal redundancy disk group requires a minimum of two disk devices (or two failure groups). The effective disk space in a normal redundancy disk group is half the sum of the disk space in all of its devices.

For Oracle Clusterware files, a normal redundancy disk group requires a minimum of three disk devices and provides three voting files and one OCR (one primary and one secondary copy). For example, your deployment may consist of two regular failure groups and one quorum failure group. With normal redundancy, the cluster can handle the loss of one failure group.

If you are not using a storage array providing independent protection against data loss for storage, then Oracle recommends that you select normal redundancy.

- External redundancy

An external redundancy disk group requires a minimum of one disk device. The effective disk space in an external redundancy disk group is the sum of the disk space in all of its devices.

Because Oracle ASM does not mirror data in an external redundancy disk group, Oracle recommends that you use external redundancy with storage devices such as RAID, or other similar devices that provide their own data protection mechanisms.

- Flex redundancy

A flex redundancy disk group is a type of redundancy disk group with features such as flexible file redundancy, mirror splitting, and redundancy change. A flex disk group can consolidate files with different redundancy requirements into a single disk group. It also provides the capability for databases to change the redundancy of its files. A disk group is a collection of file groups, each associated with one database. A quota group defines the maximum storage space or quota limit of a group of databases within a disk group.

In a flex redundancy disk group, Oracle ASM uses three-way mirroring of Oracle ASM metadata to increase performance and provide reliability. For database data, you can choose no mirroring (unprotected), two-way mirroring (mirrored), or three-way mirroring (high). A flex redundancy disk group requires a minimum of three disk devices (or three failure groups).

- Extended redundancy

Extended redundancy disk group has similar features as the flex redundancy disk group. Extended redundancy is available when you configure an Oracle Extended Cluster. Extended redundancy extends Oracle ASM data protection to cover failure of sites by placing enough copies of data in different failure groups of each site. A site is a collection of failure groups. For extended redundancy with three sites, for example, two data sites, and one quorum failure group, the minimum number of disks is seven (three disks each for two data sites and one quorum failure group outside the two data sites). The maximum number of supported sites for extended redundancy is three. In an extended redundancy disk group, each site maintains the user data redundancy as specified by the file group attribute. Each site can host data failure groups and quorum failure groups for a given disk group. For example, if the file group redundancy is specified as 2 or 3, each site has 2 or 3 mirrors respectively, provided there are enough failure groups to accommodate the mirrors. See *About Oracle Extended Clusters* for more information about selecting redundancy levels for extended clusters.

 **See Also:**

Oracle Automatic Storage Management Administrator's Guide for more information about file groups and quota groups for flex disk groups

 **Note:**

You can alter the redundancy level of the disk group after a disk group is created. For example, you can convert a normal or high redundancy disk group to a flex redundancy disk group. Within a flex redundancy disk group, file redundancy can change among three possible values: unprotected, mirrored, or high.

4. Determine the total amount of disk space that you require for Oracle Clusterware files, and for the database files and recovery files.

If an Oracle ASM instance is running on the system, then you can use an existing disk group to meet these storage requirements. If necessary, you can add disks to an existing disk group during the database installation.

See *Oracle Clusterware Storage Space Requirements* to determine the minimum number of disks and the minimum disk space requirements for installing Oracle Clusterware files, and installing the starter database, where you have voting files in a separate disk group.

5. Determine an allocation unit size.

Every Oracle ASM disk is divided into allocation units (AU). An allocation unit is the fundamental unit of allocation within a disk group. You can select the AU Size value from 1, 2, 4, 8, 16, 32, or 64 MB, depending on the specific disk group compatibility level. For flex disk groups, the default value for AU size is set to 4 MB. For external, normal, and high redundancies, the default AU size is 1 MB.

6. For Oracle Clusterware installations, you must also add additional disk space for the Oracle ASM metadata. You can use the following formula to calculate the disk space requirements (in MB) for OCR and voting files, and the Oracle ASM metadata:

$$\text{total} = [2 * \text{ausize} * \text{disks}] + [\text{redundancy} * (\text{ausize} * (\text{all_client_instances} + \text{nodes} + \text{disks} + 32) + (64 * \text{nodes}) + \text{clients} + 543)]$$

redundancy = Number of mirrors: external = 1, normal = 2, high = 3, flex = 3.

ausize = Metadata AU size in megabytes

all_client_instance = Sum of all database clients and ACFS proxy instances

nodes = Number of nodes in cluster.

clients - Number of database instances for each node.

disks - Number of disks in disk group.

7. Optionally, identify failure groups for the Oracle ASM disk group devices.

If you intend to use a normal or high redundancy disk group, then you can further protect the database against hardware failure by associating a set of disk devices in a custom failure group. By default, each device is included in its failure group. However, if two disk devices in a normal redundancy disk group are attached to the same Host Bus Adapter (HBA), then the disk group becomes unavailable if the adapter fails. The HBA in this example is a single point of failure.

For instance, to avoid failures of this type, you can use two HBA fabric paths, each with two disks, and define a failure group for the disks attached to each adapter. This configuration would enable the disk group to tolerate the failure of one HBA fabric path.

 **Note:**

You can define custom failure groups during installation of Oracle Grid Infrastructure. You can also define failure groups after installation using the GUI tool ASMCA, the command line tool `asmcmd`, or SQL commands. If you define custom failure groups, then you must specify a minimum of two failure groups for normal redundancy disk groups and three failure groups for high redundancy disk groups.

8. If you are sure that a suitable disk group does not exist on the system, then install or identify appropriate disk devices to add to a new disk group. Use the following guidelines when identifying appropriate disk devices:
 - The disk devices must be owned by the user performing Oracle Grid Infrastructure installation.
 - All the devices in an Oracle ASM disk group must be the same size and have the same performance characteristics.
 - Do not specify multiple partitions on a single physical disk as a disk group device. Oracle ASM expects each disk group device to be on a separate physical disk.
 - Although you can specify a logical volume as a device in an Oracle ASM disk group, Oracle does not recommend their use because it adds a layer of complexity that is unnecessary with Oracle ASM. Oracle recommends that if you choose to use a logical volume manager, then use the logical volume manager to represent a single logical unit number (LUN) without striping or mirroring, so that you can minimize the effect on storage performance of the additional storage layer.
9. If you use Oracle ASM disk groups created on Network File System (NFS) for storage, then ensure that you follow recommendations described in *Guidelines for Configuring Oracle ASM Disk Groups on NFS*.

Related Topics

- [Storage Checklist for Oracle Grid Infrastructure](#)
Review the checklist for storage hardware and configuration requirements for Oracle Grid Infrastructure installation.
- [Oracle Clusterware Storage Space Requirements](#)
Use this information to determine the minimum number of disks and the minimum disk space requirements based on the redundancy type, for installing Oracle Clusterware files for various Oracle Cluster deployments.
- [Configuring Storage Device Path Persistence Using Oracle ASMFD](#)
Oracle ASM Filter Driver (Oracle ASMFD) maintains storage file path persistence and helps to protect files from accidental overwrites.

Oracle Clusterware Storage Space Requirements

Use this information to determine the minimum number of disks and the minimum disk space requirements based on the redundancy type, for installing Oracle Clusterware files for various Oracle Cluster deployments.

Total Oracle Clusterware Available Storage Space Required by Oracle Cluster Deployment Type

Based on the cluster configuration you want to install, the Oracle Clusterware space requirements vary for different redundancy levels. The following tables list the space requirements for each cluster configuration and redundancy level.

Note:

The `DATA` disk group stores OCR and voting files, and the `RECO` disk group stores Oracle Clusterware backup files.

Table 8-1 Minimum Available Space Requirements for Oracle Grid Infrastructure Deployment to Manage Oracle RAC Databases

Redundancy Level	DATA Disk Group	Oracle Fleet Patching and Provisioning	Total Storage
External	1 GB	1 GB	2 GB
Normal	2 GB	2 GB	4 GB
High/Flex/Extended	3 GB	3 GB	6 GB

- Oracle recommends that you use a separate disk group, other than `DATA`, for Oracle Clusterware backup files.
- The initial sizing for the Oracle Grid Infrastructure deployment to manage Oracle RAC databases is for up to four nodes. You must add additional storage space to the disk group containing Oracle Clusterware backup files for each new node added to the cluster.
- By default, all new Oracle Grid Infrastructure deployments to manage Oracle RAC databases are configured with Oracle Fleet Patching and Provisioning for patching that cluster only. This deployment requires a minimal ACFS file system that is automatically configured.

Using an Existing Oracle ASM Disk Group

Use Oracle Enterprise Manager Cloud Control or the Oracle ASM command line tool (`asmcmd`) to identify existing disk groups, and to determine if sufficient space is available in the disk group.

1. Connect to the Oracle ASM instance and start the instance if necessary:

```
$ $ORACLE_HOME/bin/asmcmd
ASMCMD> startup
```

2. Enter one of the following commands to view the existing disk groups, their redundancy level, and the amount of free disk space in each one:

```
ASMCMD> lsdg
```

or

```
$ORACLE_HOME/bin/asmcmd -p lsdg
```

The `lsdg` command lists information about mounted disk groups only.

3. From the output, identify a disk group with the appropriate redundancy level and note the free space that it contains.
4. If necessary, install or identify the additional disk devices required to meet the storage requirements for your installation.

 **Note:**

If you are adding devices to an existing disk group, then Oracle recommends that you use devices that have the same size and performance characteristics as the existing devices in that disk group.

About Upgrading Existing Oracle Automatic Storage Management Instances

Oracle Automatic Storage Management (Oracle ASM) upgrades are carried out during an Oracle Grid Infrastructure upgrade.

Oracle ASM is always upgraded with Oracle Grid Infrastructure as part of the upgrade, and Oracle Automatic Storage Management Configuration Assistant (Oracle ASMCA) is started by the root scripts during upgrade. Subsequently, you can use Oracle ASMCA (located in `Grid_home/bin`) to configure failure groups, Oracle ASM volumes, and Oracle Advanced Cluster File System (Oracle ACFS).

Oracle ASMCA cannot perform a separate upgrade of Oracle ASM from a prior release to the current release.

Related Topics

- *Oracle Automatic Storage Management Administrator's Guide*
- *Oracle Database Upgrade Guide*

Selecting Disks to use with Oracle ASM Disk Groups

If you are sure that a suitable disk group does not exist on the system, then install or identify appropriate disk devices to add to a new disk group.

Use the following guidelines when identifying appropriate disk devices:

- All of the devices in an Oracle ASM disk group should be the same size and have the same performance characteristics.
- Do not specify multiple partitions on a single physical disk as a disk group device. Oracle ASM expects each disk group device to be on a separate physical disk.

- Nonshared logical partitions are not supported with Oracle RAC. To use logical partitions for your Oracle RAC database, you must use shared logical volumes created by a logical volume manager such as `fdisk`.
- Although you can specify a logical volume as a device in an Oracle ASM disk group, Oracle does not recommend their use because it adds a layer of complexity that is unnecessary with Oracle ASM. In addition, Oracle RAC requires a cluster logical volume manager in case you decide to use a logical volume with Oracle ASM and Oracle RAC.

Specifying the Oracle ASM Disk Discovery String

When an Oracle ASM instance is initialized, Oracle ASM discovers and examines the contents of all of the disks that are in the paths that you designated with values in the `ASM_DISKSTRING` initialization parameter.

The value for the `ASM_DISKSTRING` initialization parameter is an operating system–dependent value that Oracle ASM uses to limit the set of paths that the discovery process uses to search for disks. The exact syntax of a discovery string depends on the platform, ASMLib libraries, and whether NVMe over Fabrics disks or Oracle Exadata disks are used. The path names that an operating system accepts are always usable as discovery strings.

The default value of `ASM_DISKSTRING` might not find all disks in all situations. In addition, if your installation uses multipathing software, then the software might place pseudo-devices in a path that is different from the operating system default.

See Also:

- *Oracle Automatic Storage Management Administrator's Guide* for more information about the initialization parameter `ASM_DISKSTRING`
- See "Oracle ASM and Multipathing" in *Oracle Automatic Storage Management Administrator's Guide* for information about configuring Oracle ASM to work with multipathing, and consult your multipathing vendor documentation for details.

Creating Files on a NAS Device for Use with Oracle Automatic Storage Management

If you have a certified NAS storage device, then you can create zero-padded files in an NFS mounted directory and use those files as disk devices in an Oracle ASM disk group.

Ensure that you specify the ASM discovery path for Oracle ASM disks.

During installation of Oracle Grid Infrastructure, Oracle Universal Installer (OUI) can create files in the NFS mounted directory you specify. The following procedure explains how to manually create files in an NFS mounted directory to use as disk devices in an Oracle ASM disk group:

1. If necessary, create an exported directory for the disk group files on the NAS device.
2. Switch user to `root`.
3. Create a mount point directory on the local system.

For example:

```
# mkdir -p /mnt/oracleasm
```

4. To ensure that the NFS file system is mounted when the system restarts, add an entry for the file system in the mount file `/etc/fstab`.
5. Enter a command similar to the following to mount the NFS on the local system:

```
# mount /mnt/oracleasm
```

6. Choose a name for the disk group to create, and create a directory for the files on the NFS file system, using the disk group name as the directory name.

For example, if you want to set up a disk group for a sales database:

```
# mkdir /mnt/oracleasm/sales1
```

7. Use commands similar to the following to create the required number of zero-padded files in this directory:

```
# dd if=/dev/zero  
of=/mnt/oracleasm/sales1/disk1 bs=1024k  
count=1000
```

This example creates 1 GB files on the NFS file system. You must create one, two, or three files respectively to create an external, normal, or high redundancy disk group.

 **Note:**

Creating multiple zero-padded files on the same NAS device does not guard against NAS failure. Instead, create one file for each NAS device and mirror them using the Oracle ASM technology.

8. Enter commands similar to the following to change the owner, group, and permissions on the directory and files that you created:

```
# chown -R grid:asmdba /mnt/oracleasm  
# chmod -R 660 /mnt/oracleasm
```

In this example, the installation owner is `grid` and the OSDBA group for Oracle ASM is `asmdba`.

9. During Oracle Database installations, edit the Oracle ASM disk discovery string to specify a regular expression that matches the file names you created.

For example:

```
/mnt/oracleasm/sales1/
```

Related Topics

- [My Oracle Support Note 359515.1](#)

Configuring Storage Device Path Persistence Using Oracle ASMFD

Oracle ASM Filter Driver (Oracle ASMFD) maintains storage file path persistence and helps to protect files from accidental overwrites.

- [About Oracle ASM with Oracle ASM Filter Driver](#)
During Oracle Grid Infrastructure installation, you can choose to install and configure Oracle Automatic Storage Management Filter Driver (Oracle ASMFD). Oracle ASMFD helps prevent corruption in Oracle ASM disks and files within the disk group.
- [Configuring Oracle ASM Filter Driver](#)
You can configure Oracle ASM Filter Driver (Oracle ASMFD) for device persistence during the installation of Oracle Grid Infrastructure or after Oracle Grid Infrastructure has been installed.
- [About Migrating From Oracle ASMLib to Oracle ASM Filter Driver](#)
If ASMLIB is installed and configured for an existing Oracle ASM installation, then you must explicitly uninstall the existing ASMLIB configuration before installing and configuring Oracle ASMFD.
- [Determining If Oracle ASM Filter Driver Is Configured](#)
The value of the `AFD_STATE` parameter of `SYS_ASMFD_PROPERTIES` specifies whether Oracle ASMFD is configured for the Oracle ASM instance.

About Oracle ASM with Oracle ASM Filter Driver

During Oracle Grid Infrastructure installation, you can choose to install and configure Oracle Automatic Storage Management Filter Driver (Oracle ASMFD). Oracle ASMFD helps prevent corruption in Oracle ASM disks and files within the disk group.

Oracle ASM Filter Driver (Oracle ASMFD) rejects write I/O requests that are not issued by Oracle software. This write filter helps to prevent users with administrative privileges from inadvertently overwriting Oracle ASM disks, thus preventing corruption in Oracle ASM disks and files within the disk group. For disk partitions, the area protected is the area on the disk managed by Oracle ASMFD, assuming the partition table is left untouched by the user.

Oracle ASMFD simplifies the configuration and management of disk devices by eliminating the need to rebind disk devices used with Oracle ASM each time the system is restarted.

If Oracle ASMLIB exists on your Linux system, then deinstall Oracle ASMLIB before installing Oracle Grid Infrastructure, so that you can choose to install and configure Oracle ASMFD during an Oracle Grid Infrastructure installation.

Caution:

When you configure Oracle ASM, including Oracle ASMFD, do not modify or erase the contents of the Oracle ASM disks, or modify any files, including the configuration files.

Related Topics

- [Deinstalling Oracle ASMLIB On Oracle Grid Infrastructure](#)
If Oracle ASM library driver (Oracle ASMLIB) is installed but you do not use it for device path persistence, then deinstall Oracle ASMLIB.
- *Oracle Automatic Storage Management Administrator's Guide*

Configuring Oracle ASM Filter Driver

You can configure Oracle ASM Filter Driver (Oracle ASMF) for device persistence during the installation of Oracle Grid Infrastructure or after Oracle Grid Infrastructure has been installed.

- [Configuring Oracle ASM Filter Driver During Installation](#)
You can optionally enable automated installation and configuration of Oracle ASM Filter Driver (Oracle ASMF) for your system during the installation of Oracle Grid Infrastructure.
- [Configuring Oracle ASM Filter Driver After Installation](#)
You can install and configure Oracle ASM Filter Driver for your system after installing Oracle Grid Infrastructure.

Configuring Oracle ASM Filter Driver During Installation

You can optionally enable automated installation and configuration of Oracle ASM Filter Driver (Oracle ASMF) for your system during the installation of Oracle Grid Infrastructure.

If you do not use `udev` on the Oracle Grid Infrastructure server, then you can provision disks for Oracle ASMF before the installer is launched. This procedure must be performed after the Oracle Grid Infrastructure installation zip files have been unzipped in the Oracle Grid Infrastructure home, but before you enable the **Configure ASM Filter Driver** check box during the installation process when the setup script is run.

1. As the `root` user, set the environment variable `$ORACLE_HOME` to the location of the Grid home and the environment variable `$ORACLE_BASE` to a temporary location.

```
$ su root
# export ORACLE_HOME=/u01/app/23.0.0/grid
# export ORACLE_BASE=/tmp
```

The `ORACLE_BASE` environment variable is set to a temporary location to avoid creating diagnostic or trace files in the Grid home before the Oracle Grid Infrastructure installation.

2. Add the `ORACLE_HOME/bin` directory to the `PATH` environment variable.

```
# export PATH=$ORACLE_HOME/bin:$PATH
```

3. Ensure that the disk devices that you are using for Oracle ASMF are owned by the user performing the Oracle Grid Infrastructure installation.

```
# chown grid:asmdba /dev/sda1

# ls -l /dev/sda1
brw-rw---- 1 grid asmdba 8, 49 Dec  8 04:49 /dev/sda1
```

Alternatively, you can change disk ownership to the `root` user and the `oinstall` group, and assign read and write permissions to the user performing the Oracle Grid Infrastructure installation.

4. Use the ASMCMD `afd_label` command to provision disk devices for use with Oracle ASM Filter Driver.

```
# $ORACLE_HOME/bin/asmcmd afd_label DATA1 /dev/sda1 --init
```

5. Use the ASMCMD `afd_lslbl` command to verify if the device has been marked for use with Oracle ASMFD.

```
# $ORACLE_HOME/bin/asmcmd afd_lslbl /dev/sda1
```

6. Unset the `ORACLE_BASE` environment variable after you finish provisioning disks for Oracle ASMFD.

```
# unset ORACLE_BASE
```

7. On the **Create ASM Disk Group** page during the Oracle Grid Infrastructure installation, select the **Configure ASM Filter Driver** check box to enable configuration of Oracle ASM Filter Driver, and then add your provisioned disks to the initial disk group (typically named `DATA`).

Note:

If the disks are not listed on the **Create ASM Disk Group** page when you use the default discovery string `/dev/sd*`, then click **Change Discovery Path** and enter your specific disk discovery string.

Configuring Oracle ASM Filter Driver After Installation

You can install and configure Oracle ASM Filter Driver for your system after installing Oracle Grid Infrastructure.

1. As the `grid` user, update the Oracle ASM disk discovery string to enable Oracle ASMFD to discover devices in the future.
 - a. Retrieve the current value of the Oracle ASM disk discovery string.

```
$ $ORACLE_HOME/bin/asmcmd dsget
```

The value of `disk_string` in the above command is the current Oracle ASM disk discovery string value retrieved by `dsget`. If the disks are in the default location for the operating system environment and disk discovery string has not been set, then the disk discovery string is empty.

- b. Update the Oracle ASM disk discovery string. If the string is empty, then update the value of the disk discovery string to include the default disk location.

```
$ $ORACLE_HOME/bin/asmcmd dsset 'disk_string,AFD:*
```

2. As the `grid` user, list the nodes and node roles in your cluster.

```
$ $ORACLE_HOME/bin/olsnodes -a
```

3. Perform the following steps, either in rolling or non-rolling mode, on each cluster node.

- a. As the `root` user, stop the Oracle Clusterware stack.

```
# $ORACLE_HOME/bin/crsctl stop crs
```

- b. Configure Oracle ASMFD to filter at the node level.

```
# $ORACLE_HOME/bin/asmcmd afd_configure
```

- c. As the `grid` user, verify the status of Oracle ASMFD.

```
$ $ORACLE_HOME/bin/asmcmd afd_state
ASMCMD-9526: The AFD state is 'LOADED' and filtering is 'ENABLED' on
host 'myhost'
```

- d. As the `root` user, label all the Oracle ASM disks for Oracle ASMFD.

```
# $ORACLE_HOME/bin/asmcmd afd_label 'label_name' 'device_path' --migrate
```

The `afd_label` command sets a user-defined label to the Oracle ASMFD disk that you specify.

- e. Scan all the Oracle ASM disks.

```
$ $ORACLE_HOME/bin/asmcmd afd_scan disk_string
```

The `afd_scan` command scans for Oracle ASMFD disks using the discovery string that you specify. If you run the command without specifying a disk discovery string, then `afd_scan` uses the Oracle ASMFD disk discovery string value in the `afd.conf` file.

- f. Start the Oracle Clusterware stack on the node.

```
# $ORACLE_HOME/bin/crsctl start crs
```

- g. As the `grid` user, set the Oracle ASMFD discovery disk string to the updated Oracle ASM disk discovery string value from Step 1.

```
$ $ORACLE_HOME/bin/asmcmd afd_dsset disk_string
```

After you set the Oracle ASMFD discovery disk string, Oracle ASMFD will identify and start managing disks, including those previously managed by Oracle ASMLIB.

See Also:

Oracle Automatic Storage Management Administrator's Guide for information about Oracle ASMFD management commands.

About Migrating From Oracle ASMLib to Oracle ASM Filter Driver

If ASMLIB is installed and configured for an existing Oracle ASM installation, then you must explicitly uninstall the existing ASMLIB configuration before installing and configuring Oracle ASMFD.

Oracle recommends that you temporarily move Oracle Cluster Registry (OCR) and voting files to another disk group if one is available, and migrate the disk group to use Oracle ASMFD. After migrating the disk group to use Oracle ASMFD, move OCR and voting files back to the disk group. You can similarly migrate any other disk groups if they contain OCR or voting files to ensure online migration of all disk groups to Oracle ASMFD.

- [Migrating Oracle ASM Disk Groups Including OCR or Voting Files](#)
Follow this procedure to migrate Oracle ASM disk groups with Oracle Cluster Registry (OCR) or voting files to Oracle ASMFD.
- [Migrating Oracle ASM Disk Groups with Oracle Cluster Registry or Voting Files](#)
Follow this procedure to migrate Oracle ASM disk groups with Oracle Cluster Registry (OCR) or voting files to Oracle ASMFD.

See Also:

- *Oracle Clusterware Administration and Deployment Guide* for information about replacing Oracle Cluster Registry locations and migrating voting files
- *Oracle Clusterware Administration and Deployment Guide* for information about using CRSCTL commands
- *Oracle Clusterware Administration and Deployment Guide* and *Oracle Real Application Clusters Administration and Deployment Guide* for information about SRVCTL commands
- [Deinstalling Oracle ASMLIB On Oracle Grid Infrastructure](#) for information about deinstalling Oracle ASMLIB.

Migrating Oracle ASM Disk Groups Including OCR or Voting Files

Follow this procedure to migrate Oracle ASM disk groups with Oracle Cluster Registry (OCR) or voting files to Oracle ASMFD.

1. As the `root` user, list the disk groups with OCR and voting files on one node.

```
# $ORACLE_HOME/bin/ocrcheck -config  
# $ORACLE_HOME/bin/crsctl query css votedisk
```

2. As the `grid` user, list the existing disk groups.

```
$ $ORACLE_HOME/bin/asmcmd lsdg
```

3. List the disks associated with each disk group.

```
$ $ORACLE_HOME/bin/asmcmd lsdsk -G diskgroup
```

4. Check if Oracle ASM is active.

```
$ $ORACLE_HOME/bin/srvctl status asm
```

5. Stop the databases and dismount the disk group on all nodes.

```
$ $ORACLE_HOME/bin/srvctl stop diskgroup -diskgroup diskgroup -f
```

6. Scan the disks on all cluster nodes.

```
$ $ORACLE_HOME/bin/asmcmd afd_scan
```

7. Start the databases and mount the disk group on all nodes.

```
$ $ORACLE_HOME/bin/srvctl start diskgroup -diskgroup diskgroup
```

Migrating Oracle ASM Disk Groups with Oracle Cluster Registry or Voting Files

Follow this procedure to migrate Oracle ASM disk groups with Oracle Cluster Registry (OCR) or voting files to Oracle ASMFD.

1. As the `root` user, list the disk groups with OCR and voting files on one node.

```
# $ORACLE_HOME/bin/ocrcheck -config
# $ORACLE_HOME/bin/crsctl query css votedisk
```

2. As the `grid` user, list the disks associated with each disk group.

```
$ $ORACLE_HOME/bin/asmcmd lsdsk -G diskgroup
```

3. Check if Oracle ASM is active.

```
$ $ORACLE_HOME/bin/srvctl status asm
```

4. As the `root` user, stop the databases and Oracle Clusterware on all nodes.

```
# $ORACLE_HOME/bin/crsctl stop cluster -all
```

5. As the `grid` user, label all existing disks in the disk group by running the following command for each disk on one node.

```
$ $ORACLE_HOME/bin/asmcmd afd_label label disk_path --migrate
```

6. Scan the disks on all cluster nodes.

```
$ $ORACLE_HOME/bin/asmcmd afd_scan
```

7. As the `root` user, start the Oracle Clusterware stack on all nodes and mount the OCR and voting files disk groups and databases.

```
# $ORACLE_HOME/bin/crsctl start cluster -all
```

Determining If Oracle ASM Filter Driver Is Configured

The value of the `AFD_STATE` parameter of `SYS_ASMFD_PROPERTIES` specifies whether Oracle ASMFD is configured for the Oracle ASM instance.

1. As the `grid` user, check the state of Oracle ASMFD with the `ASMCMD afd_state` command.

```
$ $ORACLE_HOME/bin/asmcmd afd_state
ASMCMD-9526: The AFD state is 'LOADED' and filtering is 'DEFAULT' on host
'myhost'
```

2. Run the following query on the Oracle ASM instance to determine if Oracle ASMFD is present on the host and display the value of `AFD_STATE` from `SYS_CONTEXT`.

```
SQL> SELECT SYS_CONTEXT('SYS_ASMFD_PROPERTIES', 'AFD_STATE') FROM DUAL;
SYS_CONTEXT('SYS_ASMFD_PROPERTIES', 'AFD_STATE')
```

- If the value of `AFD_STATE` is equal to `NOT AVAILABLE`, then Oracle ASMFD is not configured.
- If the value of `AFD_STATE` is equal to `CONFIGURED`, then Oracle ASMFD is set up and the Oracle ASM instance can register with the driver.

Configuring NVMe Over Fabrics Storage Devices with Oracle ASM

You can use NVMe over Fabrics storage devices with Oracle Automatic Storage Management (Oracle ASM) to create Oracle ASM disk groups.

- [About Using NVMe Over Fabrics Devices for Data Files](#)
Use NVMe over Fabrics storage devices with Oracle ASM on Linux operating system to store Oracle Database data files.
- [Requirements and Guidelines for NVMe Over Fabrics Storage](#)
Review these requirements and guidelines for configuring NVMe over Fabrics storage (NVMe-oF) devices to use with Oracle Automatic Storage Management (Oracle ASM).
- [Creating an NVMe-oF Storage Target](#)
Configure the NVMe over Fabrics (NVMe-oF) storage targets to create Oracle ASM disk groups that store Oracle Grid Infrastructure and Oracle Database files.
- [Creating an NVMe Configuration File and Using NVMe-oF Devices](#)
NVMe over Fabrics uses a configuration file, `nvmip.ora`, to determine the NVMe-oF configuration and options.

About Using NVMe Over Fabrics Devices for Data Files

Use NVMe over Fabrics storage devices with Oracle ASM on Linux operating system to store Oracle Database data files.

Starting with Oracle Database 23ai, you can use TCP/IP network connections to access the remote NVMe storage devices using **Oracle Native user space NVMe over Fabrics (NVMe-oF) solution** directly from Oracle processes. The Oracle Grid Infrastructure server works as an

initiator that connects to an NVMe-oF storage target created using Linux Kernel `nvmet_tcp` module.

You can use NVMe-oF storage devices to create Oracle ASM disk groups. These disk groups can store Oracle Database data files. This configuration extends Oracle ASM capabilities to the NVMe-oF storage devices. Direct access to NVMe-oF storage targets from Oracle Database servers offers lower latency and greater throughput for I/O operations.

Oracle Grid Infrastructure 23ai works only with NVMe of Fabrics storage targets with Linux kernel 5.4 or later versions. Use an Ethernet Network Interface Card (NIC) on your Oracle Grid Infrastructure server to connect to an NVMe-oF storage target. Oracle recommends that you use a 25 GbE or higher Ethernet NIC to minimize latency.

 **Note:**

The performance of databases stored on the NVMe-oF devices depends on the performance of the network connection between the Oracle Grid Infrastructure servers and the NVMe-oF storage targets. For optimal performance, Oracle recommends that you connect the Oracle Grid Infrastructure servers to the NVMe-oF storage targets using private dedicated network connections.

Requirements and Guidelines for NVMe Over Fabrics Storage

Review these requirements and guidelines for configuring NVMe over Fabrics storage (NVMe-oF) devices to use with Oracle Automatic Storage Management (Oracle ASM).

Requirements

- Initiator operating system version supported by the current Oracle Database release.
- NVMe-oF storage targets with Linux Kernel version 5.4 or later using `nvmet_tcp` module.
- 25 GbE or more network interface card on both the Oracle Grid Infrastructure server and the NVMe over Fabrics storage target.
- Initiator IP addresses that can communicate with all the NVMe-oF storage target IP addresses.

Guidelines

- All Oracle ASM storage configuration guidelines apply to NVMe-oF storage devices.

Creating an NVMe-oF Storage Target

Configure the NVMe over Fabrics (NVMe-oF) storage targets to create Oracle ASM disk groups that store Oracle Grid Infrastructure and Oracle Database files.

The following configuration steps create an NVMe-oF storage target with 4 devices: `/dev/nvme0n1`, `/dev/nvme1n1`, `/dev/nvme2n1`, and `/dev/nvme3n1`. Complete these steps on all the storage target servers.

1. Log in as `root`.
2. Load the NVMe TCP module, if it is not already loaded.

```
modprobe nvmet_tcp
```

3. Install the `nvmetcli` package.

```
yum install nvmetcli
```

4. Start `nvmetcli` to configure the subsystems and the NVMe ports on the target.

```
nvmetcli
```

5. Create a unique NVMe Qualified Name (NQN) on the storage target in the `subsystems` directory.

```
cd subsystems/  
create nqn=storagenode1.domainname.com:nvme
```

 **Note:**

You must specify a unique NQN for each storage target.

6. Enable all storage targets to use the subsystem.

```
cd storagenode1.domainname.com:nvme/  
set attr allow_any_host=1
```

7. Create namespace ID (NSID) for each storage block.

```
cd namespaces/  
create nsid=1  
create nsid=2  
create nsid=3  
create nsid=4
```

8. Set the namespace device paths and enable them.

```
cd 1/  
set device path=/dev/nvme0n1  
enable
```

Repeat these commands for all the NSIDs.

9. Create a port ID for the NVMe target port.

```
cd /  
create portid=1  
cd 1/  
set addr adrfam=ipv4  
set addr trtype=tcp  
set addr traddr=192.168.1.11  
set addr trsvcid=4091
```

The input value for the port ID must be a positive integer, either 1 or greater.

10. Create a unique NVMe Qualified Name (NQN) for the NVMe target port in the `/ports/1/subsystems` directory.

```
cd /ports/1/subsystems
create nqn=storagenode1.domainname.com:nvme
```

11. Verify the NVMe storage target configuration that you configured.

```
cd /
ls
o- / .....
..... [...]
o-
hosts .....
..... [...]
o-
ports .....
..... [...]
| o- 1 ..... [trtype=tcp,
traddr=192.168.1.11, trsvcid=4091, inline_data_size=16384]
| o-
ana_groups .....
..... [...]
| | o-
1 .....
..... [state=optimized]
| o-
referrals .....
..... [...]
| o-
subsystems .....
..... [...]
| o-
storagenode1.domainname.com:nvme .....
..... [...]
o-
subsystems .....
..... [...]
o- storagenode1.domainname.com:nvme .....
[version=1.3, allow_any=1, serial=82d982a387d72d99c09d]
o-
allowed_hosts.....
..... [...]
o-
namespaces.....
..... [...]
o- 1 ..... [path=/dev/nvme0n1, uuid=79058da3-
ee7e-4e37-bd1d-e8375bfff5027, grpId=1, enabled]
o- 2 ..... [path=/dev/nvme1n1,
uuid=87f0b13b-1795-4da8-ba46-fce6c97403a5, grpId=1, enabled]
o- 3 ..... [path=/dev/nvme2n1,
uuid=fe0f4720-2322-4df5-8da5-e43191e7b577, grpId=1, enabled]
o- 4 ..... [path=/dev/nvme3n1,
uuid=3f79c5f0-4626-4991-a567-8ce9157a1559, grpId=1, enabled]
```

12. Repeat steps 1 through 11 on each NVMe storage target node.

Creating an NVMe Configuration File and Using NVMe-oF Devices

NVMe over Fabrics uses a configuration file, `nvmip.ora`, to determine the NVMe-oF configuration and options.

1. Create an NVMe Oracle Disk Manager (ODM) library:

```
$ cd $ORACLE_HOME/rdbms/lib
$ make -f ins_rdbms.mk nvm_on
```

2. Create an `nvmip.ora` file in the `/etc/oracle/nvm` directory on each Oracle Grid Infrastructure cluster node with the following attributes:

- `initiator`

Initiator IP address of the current Oracle Clusterware node.

Note:

- All the initiator IP addresses must be able to communicate with all the NVMe-oF storage target IP addresses.
- The initiator IP address in the configuration file is the IP address of the current node.

- `target`

Storage target IP addresses and port number of the NVMe-oF storage devices. Use the same target IP addresses for all the Oracle Grid Infrastructure nodes.

The following examples show how to use NVMe-oF devices from 2 storage servers and create a database with 2 database hosts. Database host 1 has IP address 192.168.1.1 and database host 2 has IP address 192.168.1.2. Storage node 1 has IP address 192.168.1.11 and storage node 2 has IP address 192.168.1.12.

Example 8-1 Configuring NVMe over Fabrics on node 1

The following example shows one initiator IP address of node 1 and two NVMe-oF storage target IP addresses:

```
# IP addresses following [initiator] are initiator IP addresses of the Oracle
Grid Infrastructure server.
# Failover among these IP addresses is handled by Oracle Grid Infrastructure
and Oracle Database.
# IP addresses following [target] are target IP address:port numbers.
# Mention all storage targets here to which Oracle Grid Infrastructure and
Oracle Database need to connect.
# A set of one or more targets create a "failure domain" when all the
# disks/devices serviced by those targets can be accessed by each of the
targets.
# Oracle DB will automatically batch the targets running in one failure
domain.
# Ensuring failover across targets from a single failure domain is
responsibility of the storage server.
```

```
[initiator]
192.168.1.1
[target]
192.168.1.11:4091
192.168.1.12:4091
```

Example 8-2 Configuring NVMe over Fabrics on node 2

The following example shows one initiator IP address of node 2 and two NVMe-oF storage target IP addresses:

```
# IP addresses following [initiator] are initiator IP addresses of the Oracle
Grid Infrastructure server.
# Failover among these IP addresses is handled by Oracle Grid Infrastructure
and Oracle Database.
# IP addresses following [target] are target IP address:port numbers.
# Mention all storage targets here to which Oracle Grid Infrastructure and
Oracle Database need to connect.
# A set of one or more targets create a "failure domain" when all the
# disks/devices serviced by those targets can be accessed by each of the
targets.
# Oracle DB will automatically batch the targets running in one failure
domain.
# Ensuring failover across targets from a single failure domain is
responsibility of the storage server.
```

```
[initiator]
192.168.1.2
[target]
192.168.1.11:4091
192.168.1.12:4091
```

To discover and use NVMe-oF storage devices with Oracle ASM, use `asm_diskstring='n:/*/*'`. The names of the NVMe-oF storage devices are combination of NQN and IP address. For example, with the above configuration, when you use `kfod disks=all` or `asm_diskstring='n:/*/*'` to discover NVMe-oF storage devices, you get the following output.

```
-----
-----
Disk Size      Path
User   Group
=====
=====
1: 20000 MB n:/storagenode1.domainname.com:nvme:ORAIP_192.168.1.11/1
2: 20000 MB n:/storagenode1.domainname.com:nvme:ORAIP_192.168.1.11/2
3: 20000 MB n:/storagenode1.domainname.com:nvme:ORAIP_192.168.1.11/3
4: 20000 MB n:/storagenode1.domainname.com:nvme:ORAIP_192.168.1.11/4
5: 20000 MB n:/storagenode2.domainname.com:nvme:ORAIP_192.168.1.12/1
6: 20000 MB n:/storagenode2.domainname.com:nvme:ORAIP_192.168.1.12/2
7: 20000 MB n:/storagenode2.domainname.com:nvme:ORAIP_192.168.1.12/3
8: 20000 MB n:/storagenode2.domainname.com:nvme:ORAIP_192.168.1.12/4
```

Using Disk Groups with Oracle Database Files on Oracle ASM

Review this information to configure Oracle Automatic Storage Management (Oracle ASM) storage for Oracle Clusterware and Oracle Database Files.

- [Identifying and Using Existing Oracle Database Disk Groups on Oracle ASM](#)
Identify existing disk groups and determine the free disk space that they contain. Optionally, identify failure groups for the Oracle ASM disk group devices.
- [Guidelines for Creating Disk Groups for Oracle Database Data Files](#)
If you are sure that a suitable disk group does not exist on the system, then install or identify appropriate disk devices to add to a new disk group.
- [Creating Directories for Oracle Database Files](#)
You can store Oracle Database and recovery files on a separate file system from the configuration files.

Identifying and Using Existing Oracle Database Disk Groups on Oracle ASM

Identify existing disk groups and determine the free disk space that they contain. Optionally, identify failure groups for the Oracle ASM disk group devices.

If you intend to use a normal or high redundancy disk group, then you can further protect your database against hardware failure by associating a set of disk devices in a custom failure group. By default, each device comprises its own failure group. However, if two disk devices in a normal redundancy disk group are attached to the same Host Bus Adapter (HBA), then the disk group becomes unavailable if the adapter fails. The adapter in this example is a single point of failure.

To protect against failures of this type, you could use two HBAs, each with two disks, and define a failure group for the disks attached to each adapter. This configuration would enable the disk group to tolerate the failure of one HBA.



Note:

If you define custom failure groups, then you must specify a minimum of two failure groups for normal redundancy and three failure groups for high redundancy.

Related Topics

- *Oracle Automatic Storage Management Administrator's Guide*

Guidelines for Creating Disk Groups for Oracle Database Data Files

If you are sure that a suitable disk group does not exist on the system, then install or identify appropriate disk devices to add to a new disk group.

Use the following guidelines when identifying appropriate disk devices:

- All of the devices in an Oracle ASM disk group should be the same size and have the same performance characteristics.
- Do not specify multiple partitions on a single physical disk as a disk group device. Oracle ASM expects each disk group device to be on a separate physical disk.

- Although you can specify a logical volume as a device in an Oracle ASM disk group, Oracle does not recommend their use because it adds a layer of complexity that is unnecessary with Oracle ASM. In addition, Oracle RAC requires a cluster logical volume manager in case you decide to use a logical volume with Oracle ASM and Oracle RAC.

Creating Directories for Oracle Database Files

You can store Oracle Database and recovery files on a separate file system from the configuration files.

Perform this procedure to place the Oracle Database or recovery files on a separate file system from the Oracle base directory:

1. Use the following command to determine the free disk space on each mounted file system:

```
# df -h
```

2. Identify the file systems to use, from the display:

Option	Description
Database Files	Select one of the following: <ul style="list-style-type: none"> • A single file system with at least 1.5 GB of free disk space • Two or more file systems with at least 3.5 GB of free disk space in total
Recovery Files	Choose a file system with at least 2 GB of free disk space

If you are using the same file system for multiple file types, then add the disk space requirements for each type to determine the total disk space requirement.

3. Note the names of the mount point directories for the file systems that you identified.
4. If the user performing installation has permissions to create directories on the disks where you plan to install Oracle Database, then Oracle DBCA creates the Oracle Database file directory, and the Recovery file directory. If the user performing installation does not have write access, then you must create these directories manually.

For example, given the user `oracle` and Oracle Inventory Group `oinstall`, and using the paths `/u03/oradata/wrk_area` for Oracle Database files, and `/u01/oradata/rcv_area` for the recovery area, these commands create the recommended subdirectories in each of the mount point directories and set the appropriate owner, group, and permissions on them:

- Database file directory:

```
# mkdir -p /u01/oradata/  
# chown oracle:oinstall /u01/oradata/  
# chmod 775 /u01/oradata
```

The default location for the database file directory is `$ORACLE_BASE/oradata`.

- Recovery file directory (fast recovery area):

```
# mkdir -p /u01/oradata/rcv_area
# chown oracle:oinstall /u01/oradata/rcv_area
# chmod 775 /u01/oradata/rcv_area
```

The default fast recovery area is `$ORACLE_BASE/fast_recovery_area`.

Oracle recommends that you keep the fast recovery area on a separate physical disk than that of the database file directory. This method enables you to use the fast recovery area to retrieve data if the disk containing oradata is unusable for any reason.

Configuring File System Storage for Oracle Database

Complete these procedures to use file system storage for Oracle Database.

If you plan to place storage on Network File System (NFS) protocol devices, then Oracle recommends that you use Oracle Direct NFS (dNFS) to take advantage of performance optimizations built into the Oracle Direct NFS client.

For optimal database organization and performance, Oracle recommends that you install data files and the Oracle Database software in different disks.

- [Configuring NFS Buffer Size Parameters for Oracle Database](#)
Set the values for the NFS buffer size parameters `rsize` and `wsize` to at least 32768.
- [Checking TCP Network Protocol Buffer for Direct NFS Client](#)
Check your TCP network buffer size to ensure that it is adequate for the speed of your servers.
- [Creating an oranfstab File for Direct NFS Client](#)
Direct NFS uses a configuration file, `oranfstab`, to determine the available mount points.
- [Enabling and Disabling Direct NFS Client Control of NFS](#)
Use these commands to enable or disable Direct NFS Client Oracle Disk Manager Control of NFS.
- [Enabling Hybrid Columnar Compression on Direct NFS Client](#)
Perform these steps to enable Hybrid Columnar Compression (HCC) on Direct NFS Client:

Configuring NFS Buffer Size Parameters for Oracle Database

Set the values for the NFS buffer size parameters `rsize` and `wsize` to at least 32768.

For example, to use `rsize` and `wsize` buffer settings with the value 32768 for an Oracle Database data files mount point, set mount point parameters to values similar to the following:

```
nfs_server:/vol/DATA/oradata /home/oracle/netapp nfs\
rw,bg,hard,nointr,rsize=32768,wsize=32768,tcp,actimeo=0,vers=3,timeo=600
```

Direct NFS Client issues writes at `wtmax` granularity to the NFS server.

Related Topics

- [My Oracle Support note 359515.1](#)

Checking TCP Network Protocol Buffer for Direct NFS Client

Check your TCP network buffer size to ensure that it is adequate for the speed of your servers.

By default, the network buffer size is set to 1 MB for TCP, and 2 MB for UDP. The TCP buffer size can set a limit on file transfers, which can negatively affect performance for Direct NFS Client users.

To check the current TCP buffer size, enter the following command:

```
# sysctl -a |grep -e net.ipv4.tcp_[rw]mem
```

The output of this command is similar to the following:

```
net.ipv4.tcp_rmem = 4096      87380   1056768
net.ipv4.tcp_wmem = 4096      16384   1056768
```

Oracle recommends that you set the value based on the link speed of your servers. For example, perform the following steps:

1. As root, use a text editor to open `/etc/sysctl.conf`, and add or change the following:

```
net.ipv4.tcp_rmem = 4096      87380   4194304
net.ipv4.tcp_wmem = 4096      16384   4194304
```

2. Apply your changes by running the following command:

```
# sysctl -p
```

3. Restart the network:

```
# /etc/rc.d/init.d/network restart
```

Creating an `oranfstab` File for Direct NFS Client

Direct NFS uses a configuration file, `oranfstab`, to determine the available mount points.

Create an `oranfstab` file with the following attributes for each NFS server that you want to access using Direct NFS Client:

- `server`

The NFS server name.

For NFS setup with Kerberos authentication, the `server` attribute name must be the fully-qualified name of the NFS server. This `server` attribute name is used to create service principal for Ticket Granting Service (TGS) request from the Kerberos server. If you are configuring external storage snapshot cloning, then the NFS `server` name should be a valid host name. For all other scenarios, the NFS `server` name can be any unique name.

- `local`

Up to four paths on the database host, specified by IP address or by name, as displayed using the `ifconfig` command run on the database host.

- `path`

Up to four network paths to the NFS server, specified either by IP address, or by name, as displayed using the `ifconfig` command on the NFS server.

- `export`
The exported path from the NFS server.
- `mount`
The corresponding local mount point for the exported volume.
- `mnt_timeout`
Specifies (in seconds) the time Direct NFS Client should wait for a successful mount before timing out. This parameter is optional. The default timeout is 10 minutes (600).
- `nfs_version`
Specifies the NFS protocol version used by Direct NFS Client. Acceptable values are NFSv3, NFSv4, NFSv4.1, and pNFS. The default version is NFSv3. If you select NFSv4.x, then you must configure the value in `oranstab` for `nfs_version`.

Specify `nfs_version` as `pNFS`, if you want to use Direct NFS with Parallel NFS. Direct NFS supports only the default `sys` security authentication with Parallel NFS. Direct NFS does not support Parallel NFS when combined with any of the Kerberos authentication parameters.
- `security_default`
Specifies the default security mode applicable for all the exported NFS server paths for a server entry. This parameter is optional. `sys` is the default value. See the description of the `security` parameter for the supported security levels for the `security_default` parameter.
- `security`
Specifies the security level, to enable security using Kerberos authentication protocol with Direct NFS Client. This optional parameter can be specified per export-mount pair. The supported security levels for the `security_default` and `security` parameters are:
 - `sys`: UNIX level security AUTH_UNIX authentication based on user identifier (UID) and group identifier (GID) values. This is the default value for security parameters.
 - `krb5`: Direct NFS runs with plain Kerberos authentication. Server is authenticated as the real server which it claims to be.
 - `krb5i`: Direct NFS runs with Kerberos authentication and NFS integrity. Server is authenticated and each of the message transfers is checked for integrity.
 - `krb5p`: Direct NFS runs with Kerberos authentication and NFS privacy. Server is authenticated, and all data is completely encrypted.
The `security` parameter, if specified, takes precedence over the `security_default` parameter. If neither of these parameters are specified, then `sys` is the default authentication.

For NFS server Kerberos security setup, review the relevant NFS server documentation. For Kerberos client setup, review the relevant operating system documentation.
- `dontroute`
Specifies that outgoing messages should not be routed by the operating system, but instead sent using the IP address to which they are bound.

 **Note:**

The `dontroute` option is a POSIX option, which sometimes does not work on Linux systems with multiple paths in the same subnet.

- `management`
Enables Direct NFS Client to use the management interface for SNMP queries. You can use this parameter if SNMP is running on separate management interfaces on the NFS server. The default value is the server parameter value.
- `community`
Specifies the community string for use in SNMP queries. Default value is `public`.

The following examples show three possible NFS server entries in `oranfstab`. A single `oranfstab` can have multiple NFS server entries.

Example 8-3 Using Local and Path NFS Server Entries

The following example uses both local and path. Because they are in different subnets, you do not have to specify `dontroute`.

```
server: MyDataServer1
local: 192.0.2.0
path: 192.0.2.1
local: 192.0.100.0
path: 192.0.100.1
export: /vol/oradata1 mount: /mnt/oradata1
```

Example 8-4 Using Local and Path in the Same Subnet, with dontroute

Local and path in the same subnet, where `dontroute` is specified:

```
server: MyDataServer2
local: 192.0.2.0
path: 192.0.2.128
local: 192.0.2.1
path: 192.0.2.129
dontroute
export: /vol/oradata2 mount: /mnt/oradata2
```

Example 8-5 Using Names in Place of IP Addresses, with Multiple Exports, management and community

```
server: MyDataServer3
local: LocalPath1
path: NfsPath1
local: LocalPath2
path: NfsPath2
local: LocalPath3
path: NfsPath3
local: LocalPath4
path: NfsPath4
dontroute
```

```
export: /vol/oradata3 mount: /mnt/oradata3
export: /vol/oradata4 mount: /mnt/oradata4
export: /vol/oradata5 mount: /mnt/oradata5
export: /vol/oradata6 mount: /mnt/oradata6
community: private
```

Example 8-6 Using Kerberos Authentication with Direct NFS Export

The `security` parameter overrides `security_default`:

```
server: nfsserver
local: 192.0.2.0
path: 192.0.2.2
local: 192.0.2.3
path: 192.0.2.4
export: /private/oracle1/logs mount: /logs security: krb5
export: /private/oracle1/data mount: /data security: krb5p
export: /private/oracle1/archive mount: /archive security: sys
export: /private/oracle1/data1 mount: /data1
security_default: krb5i
```

Enabling and Disabling Direct NFS Client Control of NFS

Use these commands to enable or disable Direct NFS Client Oracle Disk Manager Control of NFS.

By default, Direct NFS Client is installed in an enabled state. However, if Direct NFS Client is disabled and you want to enable it, complete the following steps on each node. If you use a shared Grid home for the cluster, then complete the following steps in the shared Grid home:

1. Log in as the Oracle Grid Infrastructure installation owner.
2. Change directory to `Grid_home/rdbms/lib`.
3. Enter the following command:

```
$ make -f ins_rdbms.mk dnfs_on
```

Note:

If you remove an NFS path that an Oracle Database is using, then you must restart the database for the change to take effect.

Enabling Hybrid Columnar Compression on Direct NFS Client

Perform these steps to enable Hybrid Columnar Compression (HCC) on Direct NFS Client:

1. Ensure that SNMP is enabled on the ZFS storage server. For example:

```
$ snmpget -v1 -c public server_name .1.3.6.1.4.1.42.2.225.1.4.2.0
SNMPv2-SMI::enterprises.42.2.225.1.4.2.0 = STRING: "Sun Storage 7410"
```

2. If SNMP is enabled on an interface other than the NFS server, then configure `orantstab` using the management parameter.
3. If SNMP is configured using a community string other than public, then configure `orantstab` file using the community parameter.
4. Ensure that `libnetsnmp.so` is installed by checking if `snmpget` is available.

Creating Oracle ASM Client Data File

Generate an Oracle ASM client data file and copy the file to the Oracle ASM client cluster member node on which you are installing Oracle Grid Infrastructure.

Enable Access Control List (ACL) before creating an Oracle ASM client data file.

1. As the `grid` user, create an Oracle ASM client data file on a storage server cluster.

```
$ $ORACLE_HOME/bin/asmcmd mkcc client_cluster_name /home/grid/  
clientcluster.xml  
[--direct] [--version client_cluster_version] [--guid client_cluster_guid]  
[--asm]
```

Note:

Specify the client cluster version as `23.0.0.0.0` if it is different from the storage server version. The storage server version is used if client cluster version is not specified.

2. Copy the Oracle ASM client data file to a secure path on the client cluster node.
The `grid` user must have permissions to access the Oracle ASM client data file. Oracle recommends that you do not grant permissions to any other user to access the Oracle ASM credentials file.

Related Topics

- The ASMCMD `mkcc` Command

Configuring Oracle Advanced Cluster File System

Review this information to configure Oracle ACFS for an Oracle RAC Oracle Database home.

Oracle ACFS is installed as part of an Oracle Grid Infrastructure installation. You can also create a General Purpose File System configuration of ACFS using ASMCA.

To configure Oracle ACFS for an Oracle Database home for an Oracle RAC database:

1. Install Oracle Grid Infrastructure for a cluster.
2. Change directory to the Oracle Grid Infrastructure home. For example:

```
$ cd /u01/app/23.0.0/grid
```

3. Ensure that the Oracle Grid Infrastructure installation owner has read and write permissions on the storage mountpoint you want to use. For example, if you want to use the mountpoint `/u02/acfsmounts/`:

```
$ ls -l /u02/acfsmounts
```

4. Start Oracle ASM Configuration Assistant (ASMCA) as the grid installation owner. For example:

```
./asmca
```

5. The Configure ASM: ASM Disk Groups page shows you the Oracle ASM disk group you created during installation. Click the **ASM Cluster File Systems** tab.
6. On the ASM Cluster File Systems page, right-click the Data disk, then select **Create ACFS for Database Use**.
7. In the **Create ACFS for Database** window, enter the following information:

- **Volume Name:** Enter the name of the database home. The name must be unique in your enterprise. For example: `dbase_01`
- **Mount Point:** Enter the directory path for the mount point. For example: `/u02/acfsmounts/dbase_01`
Make a note of this mount point for future reference.
- **Size (GB):** Enter in gigabytes the size you want the database home to be. The default is 12 GB and the minimum recommended size.
- **Owner Name:** Enter the name of the Oracle Database installation owner you plan to use to install the database. For example: `oracle1`
- **Owner Group:** Enter the OSDBA group whose members you plan to provide when you install the database. Members of this group are given operating system authentication for the SYSDBA privileges on the database. For example: `dba1`

Select **Automatically run configuration commands** to run ASMCA configuration commands automatically. To use this option, you must provide the root credentials on the ASMCA Settings page.

Click **OK** when you have completed your entries.

8. If you did not select to run configuration commands automatically, then run the script generated by Oracle ASM Configuration Assistant as a privileged user (`root`). On an Oracle Clusterware environment, the script registers the ACFS as a resource managed by Oracle Clusterware. Registering ACFS as a resource helps Oracle Clusterware to mount ACFS automatically in proper order when ACFS is used for an Oracle RAC Oracle Database home.
9. During Oracle RAC installation, ensure that you or the DBA who installs Oracle RAC selects for the Oracle home the mount point you provided in the **Mount Point** field (in the preceding example, `/u02/acfsmounts/dbase_01`).

Checking OCFS2 Version Manually

Use the following command to check your OCFS2 version manually.

Ensure that `ocfs2console` and `ocfs2-tools` are at least version 1.2.7, and that the other OCFS2 components correspond to the pattern `ocfs2-kernel_version-1.2.7` or greater. If you

want to install Oracle RAC on a shared home, then the OCFS2 version must be 1.4.1 or greater.

```
modinfo ocfs2  
rpm -qa |grep ocfs2
```

For information about OCFS2, refer to the following website:
<http://oss.oracle.com/projects/ocfs2/>

9

Installing Oracle Grid Infrastructure

Review this information for installation and deployment options for Oracle Grid Infrastructure.

Oracle Database and Oracle Grid Infrastructure installation software is available in multiple media, and can be installed using several options. The Oracle Grid Infrastructure software is available as an image, available for download from the Oracle Technology Network website, or the Oracle Software Delivery Cloud portal. In most cases, you use the graphical user interface (GUI) provided by Oracle Universal Installer to install the software. You can also use Oracle Universal Installer to complete silent mode installations, without using the GUI. You can also use Oracle Fleet Patching and Provisioning for subsequent Oracle Grid Infrastructure and Oracle Database deployments.

- [About Image-Based Oracle Grid Infrastructure Installation](#)
Installation and configuration of Oracle Grid Infrastructure software is simplified with image-based installation.
- [Setup Wizard Installation Options for Creating Images](#)
Gold image-creation options to use with your Oracle Database or Oracle Grid Infrastructure installation setup wizards.
- [Downloading the Software from Oracle Software Delivery Cloud Portal](#)
You can download the software from Oracle Software Delivery Cloud.
- [Understanding Cluster Configuration Options](#)
Review these topics to understand the cluster configuration options available in Oracle Grid Infrastructure.
- [Installing Oracle Grid Infrastructure for a New Cluster](#)
Review these procedures to install the cluster configuration options available in this release of Oracle Grid Infrastructure.
- [Installing Oracle Grid Infrastructure Using Command-Line Interface](#)
Starting with Oracle Grid Infrastructure 23ai, you can install and configure Oracle Grid Infrastructure using the command-line interface.
- [Installing Oracle Grid Infrastructure Using a Cluster Configuration File](#)
During installation of Oracle Grid Infrastructure, you have the option of either providing cluster configuration information manually, or using a cluster configuration file.
- [Installing Only the Oracle Grid Infrastructure Software](#)
This installation option requires manual postinstallation steps to enable the Oracle Grid Infrastructure software.
- [About Deploying Oracle Grid Infrastructure Using Oracle Fleet Patching and Provisioning](#)
Learn how you can use Oracle Fleet Patching and Provisioning (Oracle FPP) to provision your Oracle homes, and to manage your software lifecycle.
- [Confirming Oracle Clusterware Function](#)
After Oracle Grid Infrastructure installation, confirm that your Oracle Clusterware installation is installed and running correctly.
- [Confirming Oracle ASM Function for Oracle Clusterware Files](#)
Confirm Oracle ASM is running after installing Oracle Grid Infrastructure.

- [Understanding Offline Processes in Oracle Grid Infrastructure](#)
After the installation of Oracle Grid Infrastructure, some components may be listed as OFFLINE. Oracle Grid Infrastructure activates these resources when you choose to add them.

About Image-Based Oracle Grid Infrastructure Installation

Installation and configuration of Oracle Grid Infrastructure software is simplified with image-based installation.

To install Oracle Grid Infrastructure, create the new Grid home with the necessary user group permissions, and then extract the image file into the newly-created Grid home, and run the setup wizard to register the Oracle Grid Infrastructure product.

Using image-based installation, you can do the following:

- Configure Oracle Grid Infrastructure for a new cluster.
- Configure Oracle Grid Infrastructure for a standalone server (Oracle Restart).
- Upgrade Oracle Grid Infrastructure.
- Setup software only.
- Add or remove nodes from your existing cluster, if the Oracle Grid Infrastructure software is already installed or configured.

This installation feature streamlines the installation process and supports automation of large-scale custom deployments. You can also use this installation method for deployment of customized images, after you patch the base-release software with the necessary Release Updates (RUs) or Release Update Revisions (RURs).

Note:

You must extract the image software into the directory where you want your Grid home to be located, and then run the `ORACLE_HOME\gridSetup.sh` script to start the Oracle Grid Infrastructure Setup Wizard. Ensure that the Grid home directory path you create is in compliance with the Oracle Optimal Flexible Architecture recommendations.

Related Topics

- [Installing Oracle Grid Infrastructure to Manage Oracle RAC Databases](#)
Complete this procedure to install and configure Oracle Grid Infrastructure software to manage Oracle RAC databases using the Graphical User Interface (GUI).

Setup Wizard Installation Options for Creating Images

Gold image-creation options to use with your Oracle Database or Oracle Grid Infrastructure installation setup wizards.

Options

In image-based installations, you can start your Oracle Database installation or Oracle Grid Infrastructure installations by running the setup wizards `runInstaller` and `gridSetup.sh` respectively. Both these wizards come with the following image-creation options.

Table 9-1 Image-Creation Options for Setup Wizard

Option	Description
-createGoldImage	Creates a gold image from the current Oracle home.
-destinationLocation	Specify the complete path, or location, where the gold image will be created.
-exclFiles	Specify the complete paths to the files to be excluded from the newly created gold image.
-help	Displays help for all the available options.

For example:

```
./runInstaller -createGoldImage -destinationLocation /tmp/my_db_images -
exclFiles /u01/app/oracle/product/23.0.0/dbhome_1/relnotes
```

```
./gridSetup.sh -createGoldImage -destinationLocation /tmp/my_grid_images -
exclFiles /u01/app/oracle/product/23.0.0/dbhome_1/relnotes
```

Where:

/tmp/my_db_images is a temporary file location where the image zip file is created.

/tmp/my_grid_images is a temporary file location where the image zip file is created.

/u01/app/oracle/product/23.0.0/dbhome_1/relnotes is the file to be excluded in the newly created gold image.

Downloading the Software from Oracle Software Delivery Cloud Portal

You can download the software from Oracle Software Delivery Cloud.

1. Use a browser to access the Oracle Software Delivery Cloud portal:
<https://edelivery.oracle.com/>
2. Click **Sign In** and enter your Oracle account username and password.
3. Type **Oracle Database** in the search bar. Click the **Add to Cart** button corresponding to the Oracle Database version that you want to download
4. In the Checkout page, click **Checkout** and deselect any products that you do not want to download.
5. Select the operating system platform on which you want to install the software from the **Platform/Languages** column.
6. Click **Continue**.
7. Review the license agreement.
8. Select the **I reviewed and accept the Oracle License Agreement** checkbox. Click **Continue**.
9. Click **Download** to start downloading the software.

10. After you download the files, click **View Digest** to verify that the checksum matches the value listed on the download page.

Understanding Cluster Configuration Options

Review these topics to understand the cluster configuration options available in Oracle Grid Infrastructure.

Note:

Starting with Oracle Grid Infrastructure 23ai, Domain Services Clusters (DSC), which is part of the Oracle Cluster Domain architecture, are desupported. Oracle Cluster Domains consist of a Domain Services Cluster (DSC) and Member Clusters. Member Clusters were deprecated in Oracle Grid Infrastructure 19c. The DSC continues to be available to provide services to production clusters. However, with most of those services no longer requiring the DSC for hosting, installation of DSCs are desupported in Oracle Database 23ai. Oracle recommends that you use any cluster or system of your choice for services previously hosted on the DSC, if applicable. Oracle will continue to support the DSC for hosting shared services, until each service can be used on alternative systems.

- [About Oracle Grid Infrastructure to Manage Oracle RAC Databases](#)
An Oracle Grid Infrastructure deployment to manage Oracle RAC databases hosts all Oracle Grid Infrastructure services and Oracle ASM locally and requires direct access to shared storage.
- [About Oracle Grid Infrastructure to Manage Generic Applications](#)
An Oracle Grid Infrastructure deployment to manage generic applications can host any applications for which you want to enable single-server rolling database maintenance, failover, and high availability.
- [About Oracle Extended Clusters](#)
An Oracle Extended Cluster consists of nodes that are located in multiple locations called sites.

About Oracle Grid Infrastructure to Manage Oracle RAC Databases

An Oracle Grid Infrastructure deployment to manage Oracle RAC databases hosts all Oracle Grid Infrastructure services and Oracle ASM locally and requires direct access to shared storage.

Oracle Grid Infrastructure deployment to manage Oracle RAC databases contain multiple cluster nodes. The number of nodes in a cluster can be as many as 64. The cluster nodes can host different types of applications. Oracle Grid Infrastructure nodes are tightly connected, and have direct access to shared storage. Shared storage is locally mounted on each of the cluster nodes, with an Oracle ASM instance or a shared file system location available to all the nodes.

Note:

Starting with Oracle Database Release 23ai, Oracle Quality of Service Management (QoS), or QoS Management) is desupported.

When you deploy Oracle Grid Infrastructure to manage Oracle RAC databases, you can also choose to configure it as an Oracle Extended cluster. An Oracle Extended Cluster consists of nodes that are located in multiple locations or sites.

About Oracle Grid Infrastructure to Manage Generic Applications

An Oracle Grid Infrastructure deployment to manage generic applications can host any applications for which you want to enable single-server rolling database maintenance, failover, and high availability.

Oracle Grid Infrastructure deployment to manage generic applications enables you to make your applications highly available without requiring Virtual IP addresses and shared storage. This deployment model can also extend high availability and single server rolling patching capabilities to single-instance Oracle databases.

You can configure Oracle Grid Infrastructure to manage generic applications without SCAN, GNS, VIPs, and without using separate network interfaces for Oracle ASM, private, and public communication. Such clusters can manage single-instance Oracle databases, any generic applications, or third-party databases using only one network interface.



Note:

You can easily convert this deployment model to an Oracle Grid Infrastructure cluster to manage Oracle RAC databases by adding shared storage and VIP.

About Oracle Extended Clusters

An Oracle Extended Cluster consists of nodes that are located in multiple locations called sites.

When you deploy an Oracle cluster, you can also choose to configure the cluster as an Oracle Extended Cluster. You can extend an Oracle cluster across two, or more, geographically separate sites, each equipped with its own storage. In the event that one of the sites fails, the other site acts as an active standby.

Both Oracle ASM and the Oracle Database stack, in general, are designed to use enterprise-class shared storage in a data center. Fibre Channel technology, however, enables you to distribute compute and storage resources across two or more data centers, and connect them through Ethernet cables and Fibre Channel, for compute and storage needs, respectively.

You can configure an Oracle Extended Cluster when you install Oracle Grid Infrastructure. You can also do so post installation using the `ConvertToExtended` script. You manage your Oracle Extended Cluster using `CRSCTL`.

You can assign nodes and failure groups to sites. Sites contain failure groups, and failure groups contain disks.

The following conditions apply when you select redundancy levels for Oracle Extended Clusters:

Table 9-2 Oracle ASM Disk Group Redundancy Levels for Oracle Extended Clusters with 2 Data Sites

Redundancy Level	Number of Failure Groups for OCR and Voting Files Disk Groups	Number of Failure Groups for OCR Backup
Normal redundancy	1 failure group per data site, 1 quorum failure group	1 failure group per data site
Flex redundancy	1 failure group per data site, 1 quorum failure group	1 failure group per data site, 1 quorum failure group
Extended redundancy	3 failure groups each for 2 data sites, 1 quorum failure group outside the 2 data sites	3 failure groups each for 2 data sites, 1 quorum failure group outside the 2 data sites
High redundancy	Not supported	Not supported

Related Topics

- [Identifying Storage Requirements for Oracle Automatic Storage Management](#)
To identify the storage requirements for using Oracle ASM, you must determine the number of devices and the amount of free disk space that you require.
- *Oracle Clusterware Administration and Deployment Guide*

Installing Oracle Grid Infrastructure for a New Cluster

Review these procedures to install the cluster configuration options available in this release of Oracle Grid Infrastructure.

- [About Oracle Grid Infrastructure Installation](#)
You can install and configure Oracle Grid Infrastructure either to manage Oracle RAC databases or to manage generic applications.
- [Installing Oracle Grid Infrastructure to Manage Oracle RAC Databases](#)
Complete this procedure to install and configure Oracle Grid Infrastructure software to manage Oracle RAC databases using the Graphical User Interface (GUI).
- [Installing Oracle Grid Infrastructure to Manage Generic Applications](#)
Complete this procedure to install and configure Oracle Grid Infrastructure software to manage generic applications, or single-server rolling database maintenance.

About Oracle Grid Infrastructure Installation

You can install and configure Oracle Grid Infrastructure either to manage Oracle RAC databases or to manage generic applications.

Starting with Oracle Grid Infrastructure 12c Release 2 (12.2), the installation media is replaced with a zip file for the Oracle Grid Infrastructure installer. Run the installation wizard after extracting the zip file into the target home path.

At any time during installation, if you have a question about what you are being asked to do, or what input you are required to provide during installation, click the **Help** button on the installer window.

You should have your network information, storage information, and operating system users and groups available to you before you start installation, and you should be prepared to run root scripts.

As the user who owns the software for Oracle Grid Infrastructure for a cluster (`grid`) on the first node, install Oracle Grid Infrastructure for a cluster. Note that the installer uses Secure Shell (SSH) to copy the binary files from this node to the other nodes during the installation. During installation, in the Cluster Node Information window, when you specify the nodes in your cluster, you can click **SSH Connectivity** and the installer configures SSH connectivity between the specified nodes for you.

 **Note:**

These installation instructions assume you do not already have any Oracle software installed on your system. If you have already installed Oracle ASMLIB, then you cannot install Oracle ASM Filter Driver (Oracle ASMFD) until you uninstall Oracle ASMLIB. You can use Oracle ASMLIB instead of Oracle ASMFD for managing the disks used by Oracle ASM.

Installing Oracle Grid Infrastructure to Manage Oracle RAC Databases

Complete this procedure to install and configure Oracle Grid Infrastructure software to manage Oracle RAC databases using the Graphical User Interface (GUI).

1. As the `grid` user, download the Oracle Grid Infrastructure image files and extract the files into the Grid home. For example:

```
mkdir -p /u01/app/23.0.0/grid
chown grid:oinstall /u01/app/23.0.0/grid
cd /u01/app/23.0.0/grid
unzip -q download_location/grid.zip
```

`grid.zip` is the name of the Oracle Grid Infrastructure image zip file.

 **Note:**

- You must extract the zip image software into the directory where you want your Grid home to be located.
- Download and copy the Oracle Grid Infrastructure image files to the local node only. During installation, the software is copied and installed on all other nodes in the cluster.
- Oracle home or Oracle base cannot be `symlinks`, nor can any of their parent directories, all the way to up to the `root` directory.

2. Configure the shared disks for use with Oracle ASM Filter Driver:
 - a. Log in as the `root` user and set the environment variable `ORACLE_HOME` to the location of the Grid home.

For C shell:

```
su root
setenv ORACLE_HOME /u01/app/23.0.0/grid
```

For bash shell:

```
su root
export ORACLE_HOME=/u01/app/23.0.0/grid
```

- b. Use Oracle ASM command line tool (ASMCMD) to provision the disk devices for use with Oracle ASM Filter Driver.

```
cd /u01/app/23.0.0/grid/bin
./asmcmd afd_label DATA1 /dev/sdb --init
./asmcmd afd_label DATA2 /dev/sdc --init
./asmcmd afd_label DATA3 /dev/sdd --init
```

- c. Verify the device has been marked for use with Oracle ASMFD.

```
./asmcmd afd_lslbl /dev/sdb
./asmcmd afd_lslbl /dev/sdc
./asmcmd afd_lslbl /dev/sdd
```

3. Log in as the `grid` user, and start the Oracle Grid Infrastructure installer by running the following command:

```
/u01/app/23.0.0/grid/gridSetup.sh
```

 **Note:**

You can run the `gridSetup.sh` command with `oracle_install_crs_AHF_InstallLoc=path` and `oracle_install_crs_AHF_RepositoryLoc=path` flags to change Autonomous Health Framework (AHF) install location and repository location respectively.

The installer starts and the Select Configuration Option window appears.

4. Choose the option **Configure Grid Infrastructure for a New Cluster**, then click **Next**.

The Select Cluster Configuration window appears.

5. Choose the option **Configure cluster to manage Oracle RAC databases**, then click **Next**.

Select the **Configure as Extended Cluster** option to extend an Oracle RAC cluster across two or more separate sites, each equipped with its own storage.

The Grid Plug and Play Information window appears.

6. Select SCAN option for the cluster:
 - a. **Create Local SCAN** to create a SCAN locally. Enter the values in the **Cluster Name**, **SCAN Name**, and **SCAN Port** fields that are unique throughout your entire enterprise network.
 - b. **Use Shared SCAN** to share SCAN VIPs from other clusters. Specify the complete path to the SCAN client data file in the **SCAN Client Data** field.

You can select **Configure GNS** if you have configured your domain name server (DNS) to send to the GNS virtual IP address name resolution requests for the subdomain, as explained in this guide.

 **Note:**

The Highly Available Grid Naming Service feature of Grid Naming Service (GNS) in Oracle Grid Infrastructure is deprecated in Oracle Database 23ai.

For cluster member node public and VIP network addresses, provide the information required depending on the kind of cluster you are configuring:

- If you plan to use automatic cluster configuration with DHCP addresses configured and resolved through GNS, then you only need to provide the GNS VIP names as configured on your DNS.
- If you plan to use manual cluster configuration, with fixed IP addresses configured and resolved on your DNS, then provide the SCAN names for the cluster, and the public names, and VIP names for each cluster member node. For example, you can choose a name that is based on the node names' common prefix. The cluster name can be `mycluster` and the cluster SCAN name can be `mycluster-scan`.

Click **Next**.

The Cluster Node Information window appears.

7. In the Public Hostname column of the table of cluster nodes, you should see your local node, for example `node1.example.com`.

The following is a list of additional information about node IP addresses:

- For the local node only, OUI automatically fills in public and VIP fields. If your system uses vendor clusterware, then OUI may fill additional fields.
 - Host names and virtual host names are not domain-qualified. If you provide a domain in the address field during installation, then OUI removes the domain from the address.
 - Interfaces identified as private for private IP addresses should not be accessible as public interfaces. Using public interfaces for Cache Fusion can cause performance problems.
 - When you enter the public node name, use the primary host name of each node. In other words, use the name displayed by the `/bin/hostname` command.
- a. Click **Add** to add another node to the cluster.
 - b. Enter the second node's public name (`node2`), and virtual IP name (`node2-vip`), then click **OK**. Provide the virtual IP (VIP) host name for all cluster nodes, or none.

You are returned to the Cluster Node Information window. You should now see all nodes listed in the table of cluster nodes.

- c. Make sure all nodes are selected, then click the **SSH Connectivity** button at the bottom of the window.

The bottom panel of the window displays the SSH Connectivity information.

- d. Enter the operating system user name and password for the Oracle software owner (`grid`). If you have configured SSH connectivity between the nodes, then select the **Reuse private and public keys existing in user home** option. Click **Setup**.

A message window appears, indicating that it might take several minutes to configure SSH connectivity between the nodes. After a short period, another message window appears indicating that passwordless SSH connectivity has been established between the cluster nodes. Click **OK** to continue.

- e. When returned to the Cluster Node Information window, click **Next** to continue.

The Specify Network Interface Usage window appears.

8. Select the usage type for each network interface displayed.

Verify that each interface has the correct interface type associated with it. If you have network interfaces that should not be used by Oracle Clusterware, then set the network interface type to **Do Not Use**. For example, if you have only two network interfaces, then set the public interface to have a Use for value of **Public** and set the private network interface to have a Use for value of **ASM & Private**.

Click **Next**. The Storage Option Information window appears.

9. Select storage option for Oracle Cluster Registry (OCR) and voting files:

- a. Select **Use Oracle Flex ASM for storage** to store OCR and voting files on an Oracle ASM disk group.

You can also select **Configure a separate disk group to store backups of OCR** to create another Oracle ASM disk group for OCR backups.

- b. Select **Configure as ASM Client Cluster** to store OCR and voting files on an Oracle ASM disk group configured on a storage server cluster. Specify the complete path to the ASM client data file in the **ASM Client Data** field.
- c. Select **Use Shared File System** to store OCR and voting files on a shared file system.

Click **Next**. The Create ASM Disk Group window appears.

10. Provide the name and specifications for the Oracle ASM disk group.

- a. In the **Disk Group Name** field, enter a name for the disk group, for example `DATA`.
- b. Choose the Redundancy level for this disk group. Normal is the recommended option.
- c. In the Add Disks section, choose the disks to add to this disk group.

In the Add Disks section you should see the disks that you labeled in Step 2. If you do not see the disks, click the **Change Discovery Path** button and provide a path and pattern match for the disk. For example, `/dev/sd*` for local Oracle ASM disks and `n:/*/*` for NVMe over Fabrics disks.

During installation, disks labelled as Oracle ASMFD disks or Oracle ASMLIB disks are listed as candidate disks when using the default discovery string. However, if the disk has a header status of MEMBER, then it is not a candidate disk.

- d. If you want to use Oracle ASM Filter Driver (Oracle ASMFD) to manage your Oracle ASM disk devices, then select the option **Configure Oracle ASM Filter Driver**.

If you are installing on Linux systems, and you want to use Oracle ASM Filter Driver (Oracle ASMFD) to manage your Oracle ASM disk devices, then you must deinstall Oracle ASM library driver (Oracle ASMLIB) before starting Oracle Grid Infrastructure installation.

When you have finished providing the information for the disk group, click **Next**.

11. If you selected to use ASM client cluster in Step 9, then ASM Client Storage Option window appears. Select an Oracle ASM disk group from the storage server cluster to store the OCR and voting files.

12. If you selected to use a separate disk group for OCR backup, then the Backup Data Disk Group window appears. Provide the name and specifications for the OCR backup disk group.

- a. In the **Disk Group Name** field, enter a name for the disk group, for example `RECO`.
- b. Choose the Redundancy level for this disk group. Normal is the recommended option.

- c. In the Add Disks section, choose the disks to add to this disk group.

When you have finished providing the information for the disk group, click **Next**.

The Specify ASM Password window appears.

- 13. Choose the same password for the Oracle ASM SYS and ASMSNMP account, or specify different passwords for each account, then click **Next**.

The Automatic Self Correction window appears.

- 14. Select **Enable Automatic Self Correction** option if you want to configure automatic self correction for your installation, then click **Next**.

The automated fixup framework for Configuration Verification Utility (CVU) identifies and corrects any configuration errors.

The Failure Isolation Support window appears.

- 15. Select the option **Do not use Intelligent Platform Management Interface (IPMI)**, then click **Next**.

The Specify Management Options window appears.

- 16. If you have Enterprise Manager Cloud Control installed in your enterprise, then choose the option **Register with Enterprise Manager (EM) Cloud Control** and provide the EM configuration information. If you do not have Enterprise Manager Cloud Control installed in your enterprise, then click **Next** to continue.

The Privileged Operating System Groups window appears.

- 17. Accept the default operating system group names for Oracle ASM administration and click **Next**.

The Specify Install Location window appears.

- 18. Specify the directory to use for the Oracle base for the Oracle Grid Infrastructure installation, then click **Next**. The Oracle base directory must be different from the Oracle home directory.

If you copied the Oracle Grid Infrastructure installation files into the Oracle Grid home directory as directed in Step 1, then the default location for the Oracle base directory should display as `/u01/app/grid`.

If you have not installed Oracle software previously on this computer, then the Create Inventory window appears.

- 19. Change the path for the inventory directory, if required. Then, click **Next**.

If you are using the same directory names as the examples in this book, then it should show a value of `/u01/app/oraInventory`. The group name for the `oraInventory` directory should show `oinstall`.

The Root Script Execution Configuration window appears.

- 20. Select the option to **Automatically run configuration scripts**. Enter the credentials for the root user or a sudo account, then click **Next**.

Alternatively, you can Run the scripts manually as the `root` user at the end of the installation process when prompted by the installer.

The Perform Prerequisite Checks window appears.

- 21. If any of the checks have a status of Failed and are not Fixable, then you must manually correct these issues. After you have fixed the issue, you can click the **Check Again** button to have the installer recheck the requirement and update the status. Repeat as needed until all the checks have a status of Succeeded. Click **Next**.

The Summary window appears.

22. Review the contents of the Summary window and then click **Install**.

The installer displays a progress indicator enabling you to monitor the installation process.

23. If you did not configure automation of the root scripts, then you are required to run certain scripts as the `root` user, as specified in the Run Configuration Scripts window. Do *not* click **OK** until you have run all the scripts. Run the scripts on all nodes as directed, in the order shown.

For example, on Oracle Linux you perform the following steps (note that for clarity, the examples show the current user, node and directory in the prompt):

- a. As the `grid` user on `node1`, open a terminal window, and enter the following commands:

```
cd /u01/app/oraInventory
su
```

- b. Enter the password for the `root` user, and then enter the following command to run the first script on `node1`:

```
./orainstRoot.sh
```

- c. After the `orainstRoot.sh` script finishes on `node1`, open another terminal window, and as the `grid` user, enter the following commands:

```
ssh node2
cd /u01/app/oraInventory
su
```

- d. Enter the password for the `root` user, and then enter the following command to run the first script on `node2`:

```
./orainstRoot.sh
```

- e. After the `orainstRoot.sh` script finishes on `node2`, go to the terminal window you opened in part a of this step. As the `root` user on `node1`, enter the following commands to run the second script, `root.sh`:

```
cd /u01/app/23.0.0/grid
./root.sh
```

Press **Enter** at the prompt to accept the default value.

 **Note:**

You must run the `root.sh` script on the first node and wait for it to finish. You can run the `root.sh` script in parallel on all other nodes.

- f. After the `root.sh` script finishes on `node1`, go to the terminal window you opened in part c of this step. As the `root` user on `node2`, enter the following commands:

```
cd /u01/app/23.0.0/grid
./root.sh
```

After the `root.sh` script completes, return to the Oracle Universal Installer window where the Installer prompted you to run the `orainstRoot.sh` and `root.sh` scripts. Click **OK**.

The software installation monitoring window reappears.

24. Continue monitoring the installation until the Finish window appears. Then click **Close** to complete the installation process and exit the installer.

Caution:

After installation is complete, do not remove manually or run `cron` jobs that remove `/tmp/.oracle` or `/var/tmp/.oracle` directories or their files while Oracle software is running on the server. If you remove these files, then the Oracle software can encounter intermittent delays. Oracle Clusterware installations can fail with the error:

```
CRS-0184: Cannot communicate with the CRS daemon.
```

After your Oracle Grid Infrastructure installation is complete, you can install Oracle Database on a cluster node for high availability, or install Oracle RAC.

See Also:

Oracle Real Application Clusters Installation Guide or *Oracle Database Installation Guide* for your platform for information on installing Oracle Database

Installing Oracle Grid Infrastructure to Manage Generic Applications

Complete this procedure to install and configure Oracle Grid Infrastructure software to manage generic applications, or single-server rolling database maintenance.

1. As the `grid` user, download the Oracle Grid Infrastructure image files and extract the files into the Grid home. For example:

```
mkdir -p /u01/app/23.0.0/grid
chown grid:oinstall /u01/app/23.0.0/grid
cd /u01/app/23.0.0/grid
unzip -q download_location/grid.zip
```

`grid.zip` is the name of the Oracle Grid Infrastructure image zip file.

 **Note:**

- You must extract the zip image software into the directory where you want your Grid home to be located.
- Download and copy the Oracle Grid Infrastructure image files to the local node only. During installation, the software is copied and installed on all other nodes in the cluster.
- Oracle home or Oracle base cannot be `symlinks`, nor can any of their parent directories, all the way to up to the `root` directory.

2. Configure the shared disks for use with Oracle ASM Filter Driver:

- a. Log in as the `root` user and set the environment variable `ORACLE_HOME` to the location of the Grid home.**

For C shell:

```
su root
setenv ORACLE_HOME /u01/app/23.0.0/grid
```

For bash shell:

```
su root
export ORACLE_HOME=/u01/app/23.0.0/grid
```

- b. Use Oracle ASM command line tool (ASMCMD) to provision the disk devices for use with Oracle ASM Filter Driver.**

```
cd /u01/app/23.0.0/grid/bin
./asmcmd afd_label DATA1 /dev/sdb --init
./asmcmd afd_label DATA2 /dev/sdc --init
./asmcmd afd_label DATA3 /dev/sdd --init
```

- c. Verify the device has been marked for use with Oracle ASMFD.**

```
./asmcmd afd_lsbl /dev/sdb
./asmcmd afd_lsbl /dev/sdc
./asmcmd afd_lsbl /dev/sdd
```

- 3. Log in as the `grid` user, and start the Oracle Grid Infrastructure installer by running the following command:**

```
/u01/app/23.0.0/grid/gridSetup.sh
```

 **Note:**

You can run the `gridSetup.sh` command with `oracle_install_crs_AHF_InstallLoc=path` and `oracle_install_crs_AHF_RepositoryLoc=path` flags to change Autonomous Health Framework (AHF) install location and repository location respectively.

The installer starts and the Select Configuration Option window appears.

4. Choose the option **Configure Oracle Grid Infrastructure for a New Cluster**, then click **Next**.

The Select Cluster Configuration window appears.

5. Choose the option **Configure cluster to manage generic applications**, provide a name for your cluster, and then click **Next**.

Select the **Configure as Extended Cluster** option to extend the cluster across two or more separate sites, each equipped with its own storage.

The Cluster Node Information window appears.

6. In the Public Hostname column of the table of cluster nodes, you should see your local node, for example `node1.example.com`.

The following is a list of additional information about node public hostnames:

- For the local node only, OUI automatically fills in public hostname field. When you enter the public node name, use the primary host name of each node. In other words, use the name displayed by the `/bin/hostname` command.
 - Virtual host names are not required. You can use a single network interface for Oracle ASM, private interconnect, and public communication.
- a. Click **Add** to add another node to the cluster.
 - b. Enter the second node's public name (`node2`), then click **OK**.

You are returned to the Cluster Node Information window. You should now see all nodes listed in the table of cluster nodes.

- c. Make sure all nodes are selected, then click the **SSH Connectivity** button at the bottom of the window.

The bottom panel of the window displays the SSH Connectivity information.

- d. Enter the operating system user name and password for the Oracle software owner (`grid`). If you have configured SSH connectivity between the nodes, then select the **Reuse private and public keys existing in user home** option. Click **Setup**.

A message window appears, indicating that it might take several minutes to configure SSH connectivity between the nodes. After a short period, another message window appears indicating that passwordless SSH connectivity has been established between the cluster nodes. Click **OK** to continue.

- e. When returned to the Cluster Node Information window, click **Next** to continue.

The Specify Network Interface Usage window appears.

7. Select the usage type **Public, Private & ASM** for one network interface.

 **Note:**

You can use only one network interface for Oracle Grid Infrastructure deployment to manage generic applications. If you have additional network interfaces, then set these network interface type to **Do Not Use**.

Click **Next**. The Storage Option Information window appears.

8. Select storage option for Oracle Cluster Registry (OCR) and voting files:

- a. Select **Use Oracle Flex ASM for storage** to store OCR and voting files on an Oracle ASM disk group.
You can also select **Configure a separate disk group to store backups of OCR** to create another Oracle ASM disk group for OCR backups.
 - b. Select **Configure as ASM Client Cluster** to store OCR and voting files on an Oracle ASM disk group configured on a storage server cluster. Specify the complete path to the ASM client data file in the **ASM Client Data** field.
 - c. Select **Use Shared File System** to store OCR and voting files on a shared file system.
Click **Next**. The Create ASM Disk Group window appears.
9. Provide the name and specifications for the Oracle ASM disk group.
- a. In the **Disk Group Name** field, enter a name for the disk group, for example DATA.
 - b. Choose the Redundancy level for this disk group. Normal is the recommended option.
 - c. In the Select Disks section, choose the disks to add to this disk group.
In the Add Disks section you should see the disks that you labeled in Step 2. If you do not see the disks, click the **Change Discovery Path** button and provide a path and pattern match for the disk. For example, `/dev/sd*` for local Oracle ASM disks and `n:/*/*` for NVMe over Fabrics disks.
During installation, disks labelled as Oracle ASMFD disks or Oracle ASMLIB disks are listed as candidate disks when using the default discovery string. However, if the disk has a header status of MEMBER, then it is not a candidate disk.
 - d. If you want to use Oracle ASM Filter Driver (Oracle ASMFD) to manage your Oracle ASM disk devices, then select the option **Configure Oracle ASM Filter Driver**.
If you are installing on Linux systems, and you want to use Oracle ASM Filter Driver (Oracle ASMFD) to manage your Oracle ASM disk devices, then you must deinstall Oracle ASM library driver (Oracle ASMLIB) before starting Oracle Grid Infrastructure installation.

When you have finished providing the information for the disk group, click **Next**.

10. If you selected to use ASM client cluster in Step 8, then ASM Client Storage Option window appears. Select an Oracle ASM disk group from the storage server cluster to store the OCR and voting files.
11. If you selected to use a separate disk group for OCR backup, then the Backup Data Disk Group window appears. Provide the name and specifications for the OCR backup disk group.
 - a. In the **Disk Group Name** field, enter a name for the disk group, for example RECO.
 - b. Choose the Redundancy level for this disk group. Normal is the recommended option.
 - c. In the Add Disks section, choose the disks to add to this disk group.

When you have finished providing the information for the disk group, click **Next**.

The Specify ASM Password window appears.

12. Choose the same password for the Oracle ASM SYS and ASMSNMP account, or specify different passwords for each account, then click **Next**.
The Automatic Self Correction window appears.
13. Select **Enable Automatic Self Correction** option if you want to configure automatic self correction for your installation, then click **Next**.

The automated fixup framework for Configuration Verification Utility (CVU) identifies and corrects any configuration errors.

The Failure Isolation Support window appears.

14. Select the option **Do not use Intelligent Platform Management Interface (IPMI)**, then click **Next**.

The Specify Management Options window appears.

15. If you have Enterprise Manager Cloud Control installed in your enterprise, then choose the option **Register with Enterprise Manager (EM) Cloud Control** and provide the EM configuration information. If you do not have Enterprise Manager Cloud Control installed in your enterprise, then click **Next** to continue.

The Privileged Operating System Groups window appears.

16. Accept the default operating system group names for Oracle ASM administration and click **Next**.

The Specify Installation Location window appears.

17. Specify the directory to use for the Oracle base for the Oracle Grid Infrastructure installation, then click **Next**. The Oracle base directory must be different from the Oracle home directory.

If you copied the Oracle Grid Infrastructure installation files into the Oracle Grid home directory as directed in Step 1, then the default location for the Oracle base directory should display as `/u01/app/grid`.

If you have not installed Oracle software previously on this computer, then the Create Inventory window appears.

18. Change the path for the inventory directory, if required. Then, click **Next**.

If you are using the same directory names as the examples in this book, then it should show a value of `/u01/app/oraInventory`. The group name for the `oraInventory` directory should show `oinstall`.

The Root Script Execution Configuration window appears.

19. Select the option to **Automatically run configuration scripts**. Enter the credentials for the root user or a sudo account, then click **Next**.

Alternatively, you can Run the scripts manually as the `root` user at the end of the installation process when prompted by the installer.

The Perform Prerequisite Checks window appears.

20. If any of the checks have a status of Failed and are not Fixable, then you must manually correct these issues. After you have fixed the issue, you can click the **Check Again** button to have the installer recheck the requirement and update the status. Repeat as needed until all the checks have a status of Succeeded. Click **Next**.

The Summary window appears.

21. Review the contents of the Summary window and then click **Install**.

The installer displays a progress indicator enabling you to monitor the installation process.

22. If you did not configure automation of the root scripts, then you are required to run certain scripts as the `root` user, as specified in the Run Configuration Scripts window. Do *not* click **OK** until you have run all the scripts. Run the scripts on all nodes as directed, in the order shown.

For example, on Oracle Linux you perform the following steps (note that for clarity, the examples show the current user, node and directory in the prompt):

- a. As the `grid` user on `node1`, open a terminal window, and enter the following commands:

```
cd /u01/app/oraInventory
su
```

- b. Enter the password for the `root` user, and then enter the following command to run the first script on `node1`:

```
./orainstRoot.sh
```

- c. After the `orainstRoot.sh` script finishes on `node1`, open another terminal window, and as the `grid` user, enter the following commands:

```
ssh node2
cd /u01/app/oraInventory
su
```

- d. Enter the password for the `root` user, and then enter the following command to run the first script on `node2`:

```
./orainstRoot.sh
```

- e. After the `orainstRoot.sh` script finishes on `node2`, go to the terminal window you opened in part a of this step. As the `root` user on `node1`, enter the following commands to run the second script, `root.sh`:

```
cd /u01/app/23.0.0/grid
./root.sh
```

Press **Enter** at the prompt to accept the default value.

 **Note:**

You must run the `root.sh` script on the first node and wait for it to finish. You can run `root.sh` scripts concurrently on all other nodes except for the last node on which you run the script. Like the first node, the `root.sh` script on the last node must be run separately.

- f. After the `root.sh` script finishes on `node1`, go to the terminal window you opened in part c of this step. As the `root` user on `node2`, enter the following commands:

```
cd /u01/app/23.0.0/grid
./root.sh
```

After the `root.sh` script completes, return to the Oracle Universal Installer window where the Installer prompted you to run the `orainstRoot.sh` and `root.sh` scripts. Click **OK**.

The software installation monitoring window reappears.

23. Continue monitoring the installation until the Finish window appears. Then click **Close** to complete the installation process and exit the installer.

 **Caution:**

After installation is complete, do not remove manually or run `cron` jobs that remove `/tmp/.oracle` or `/var/tmp/.oracle` directories or their files while Oracle software is running on the server. If you remove these files, then the Oracle software can encounter intermittent delays. Oracle Clusterware installations can fail with the error:

```
CRS-0184: Cannot communicate with the CRS daemon.
```

After your Oracle Grid Infrastructure installation is complete, you can install Oracle Database or other generic applications on a cluster node for high availability.

If you are following a conversion procedure of the single instance database for single-server database rolling maintenance, you can continue with the next steps of the conversion procedure.

Installing Oracle Grid Infrastructure Using Command-Line Interface

Starting with Oracle Grid Infrastructure 23ai, you can install and configure Oracle Grid Infrastructure using the command-line interface.

1. As the `grid` user, download the Oracle Grid Infrastructure image files and extract the files into the Grid home.

```
mkdir -p /u01/app/23.3.0/grid
chown grid:oinstall /u01/app/23.3.0/grid
cd /u01/app/23.3.0/grid
unzip -q download_location/grid.zip
```

`grid.zip` is the name of the Oracle Grid Infrastructure image zip file.

 **Note:**

- You must extract the zip image software into the directory where you want your Grid home to be located.
- Download and copy the Oracle Grid Infrastructure image files to the local node only. During installation, the software is copied and installed on all other nodes in the cluster.
- Oracle home or Oracle base cannot be `symlinks`, nor can any of their parent directories, all the way to up to the `root` directory.

2. Configure the shared disks for use with Oracle ASM Filter Driver:

- a. Ensure that the disk devices that you are using for Oracle ASMFD are owned by the user performing the Oracle Grid Infrastructure installation.

```
# chown grid:asmdba /dev/sdb
# chown grid:asmdba /dev/sdc
# chown grid:asmdba /dev/sdd
```

- b. Log in as the `root` user and set the environment variable `ORACLE_HOME` to the location of the Grid home.

For C shell:

```
su root
setenv ORACLE_HOME /u01/app/23.3.0/grid
```

For bash shell:

```
su root
export ORACLE_HOME=/u01/app/23.3.0/grid
```

- c. Use Oracle ASM command line tool (ASMCMD) to provision the disk devices for use with Oracle ASM Filter Driver.

```
cd /u01/app/23.0.0/grid/bin
./asmcmd afd_label DATA1 /dev/sdb --init
./asmcmd afd_label DATA2 /dev/sdc --init
./asmcmd afd_label DATA3 /dev/sdd --init
```

- d. Verify the device has been marked for use with Oracle ASMFD.

```
./asmcmd afd_lsbl /dev/sdb
./asmcmd afd_lsbl /dev/sdc
./asmcmd afd_lsbl /dev/sdd
```

3. As the `grid` user, run the `gridSetup.sh` command with the `-silent` option and specify the configuration parameters.

```
/u01/app/23.3.0/grid/gridSetup.sh -silent -configureCluster -OSDBA sysdba -
OSOPER osoper -OSASM osasm -ORACLE_BASE /u01/app/grid -clusterName myrac
-scanName cluster-scan -scanPort 1521 -clusterNodes myrac1,myrac2 -
networkInterfaceList
ens3:100.70.80.0:1,ens4:192.168.1.0:5,ens5:192.168.2.0:3
-clusterUsage RAC -storageOption FLEX_ASM_STORAGE -diskGroupName DATA -
diskList /dev/sdb,/dev/sdc,/dev/sdd -redundancy NORMAL-auSize 8 -
diskString '/dev/sd*'
-configureAFD -executeRootScript -configMethod ROOT -enableAutoFixup -
managementOption NONE -INVENTORY_LOCATION /u01/app/oraInventory
```

4. Provide the `root` user password when prompted.

Related Topics

- [Configuring Oracle ASM Filter Driver During Installation](#)
You can optionally enable automated installation and configuration of Oracle ASM Filter Driver (Oracle ASMFD) for your system during the installation of Oracle Grid Infrastructure.

Installing Oracle Grid Infrastructure Using a Cluster Configuration File

During installation of Oracle Grid Infrastructure, you have the option of either providing cluster configuration information manually, or using a cluster configuration file.

A cluster configuration file is a text file that you can create before starting `gridSetup.sh`, which provides the installer with cluster node addresses that it requires to configure the cluster. Oracle recommends that you consider using a cluster configuration file if you intend to perform repeated installations on a test cluster, or if you intend to perform an installation on many nodes. A sample cluster configuration file is available in the directory `Grid_home/install/response/sample.ccf`.

To create a cluster configuration file manually, start a text editor, and create a file that provides the name of the public and virtual IP addresses for each cluster member node, in the following format:

```
node1 node1-vip
node2 node2-vip
.
.
.
```

Specify the different nodes, separating them with either spaces or colon (:).

For example:

```
mynode1 mynode1-vip
mynode2 mynode2-vip
```

Or, for example:

```
mynode1:mynode1-vip
mynode2:mynode2-vip
```

Example 9-1 Sample Cluster Configuration File

The following sample cluster configuration file is available in the directory `Grid_home/install/response/sample.ccf`:

```
#
# Cluster nodes configuration specification file
#
# Format:
# node [vip] [site-name]
#
# node          - Node's public host name
# vip           - Node's virtual host name
# site-name     - Node's assigned site
#
# Specify details of one node per line.
# Lines starting with '#' will be skipped.
```

```
#
# (1) vip is not required for Oracle Grid Infrastructure software only
#     installs
# (2) vip should be specified as AUTO if Node Virtual host names are
Dynamically
#     assigned
# (3) site-name should be specified only when configuring Oracle Grid
Infrastructure with "Extended Cluster" option
#
# Examples:
# -----
# For installing GI software only on a cluster:
# ^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^
# node1
# node2
#
# For cluster to manage Oracle RAC databases:
# ^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^
# node1 node1-vip
# node2 node2-vip
#
# For Extended Cluster:
# ^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^^
# node1 node1-vip sitea
# node2 node2-vip siteb
#
```

Installing Only the Oracle Grid Infrastructure Software

This installation option requires manual postinstallation steps to enable the Oracle Grid Infrastructure software.

If you use the **Set Up Software Only** option during installation, then Oracle Universal Installer (OUI) installs the software binaries on multiple nodes. You can then perform the additional steps of configuring Oracle Clusterware and Oracle ASM.

- [Installing Software Binaries for Oracle Grid Infrastructure for a Cluster](#)
You can install Oracle Grid Infrastructure software binaries for a cluster software on multiple nodes at a time.
- [Configuring Software Binaries for Oracle Grid Infrastructure for a Cluster](#)
Configure the software binaries by starting Oracle Grid Infrastructure configuration wizard in GUI mode.
- [Configuring the Software Binaries Using a Response File](#)
When you install or copy Oracle Grid Infrastructure software on any node, you can defer configuration for a later time. Review this procedure for completing configuration after the software is installed or copied on nodes, using the configuration wizard (`gridSetup.sh`).
- [Setting Ping Targets for Network Checks](#)
Receive notification about network status by setting the `Ping_Targets` parameter during the Oracle Grid Infrastructure installation.

 **See Also:**

Oracle Clusterware Administration and Deployment Guide for information about cloning an Oracle Grid Infrastructure installation to other nodes that were not included in the initial installation of Oracle Grid Infrastructure, and then adding them to the cluster

Installing Software Binaries for Oracle Grid Infrastructure for a Cluster

You can install Oracle Grid Infrastructure software binaries for a cluster software on multiple nodes at a time.

1. Download the Grid home image files.
2. Run the `gridSetup.sh` command and select the Configuration Option as **Set Up Software Only**.

 **Note:**

You can use the `gridSetup.sh` command with the `-applyRU` and `-applyOneOffs` flags to install Release Updates (RUs) and one-off patches during an Oracle Grid Infrastructure installation or upgrade.

3. Complete installation of Oracle Grid Infrastructure software on one or more nodes by providing information in the installer screens in response to your configuration selection. You can install Oracle Grid Infrastructure software on multiple nodes at a time.
4. When the software is configured, run the `oraInstRoot.sh` script on all nodes, when prompted.
5. On all nodes, the `root.sh` script output provides information about how to proceed, depending on the configuration you plan to complete in this installation. Make note of this information.
6. Ensure that you have completed all storage and server preinstallation requirements.
7. Verify that all of the cluster nodes meet the installation requirements:

```
runcluvfy.sh stage -pre crsinst -n node_list
```

8. Configure the cluster using the Oracle Universal Installer (OUI) configuration wizard or response files.

Related Topics

- [Configuring Software Binaries for Oracle Grid Infrastructure for a Cluster](#)
Configure the software binaries by starting Oracle Grid Infrastructure configuration wizard in GUI mode.
- [Installing Oracle Grid Infrastructure for a New Cluster](#)
Review these procedures to install the cluster configuration options available in this release of Oracle Grid Infrastructure.
- [Applying Patches During an Oracle Grid Infrastructure Installation or Upgrade](#)
You can download and apply Release Updates (RUs) and one-off patches during an Oracle Grid Infrastructure installation or upgrade.

Configuring Software Binaries for Oracle Grid Infrastructure for a Cluster

Configure the software binaries by starting Oracle Grid Infrastructure configuration wizard in GUI mode.

1. Log in on a cluster node as the Oracle Grid Infrastructure installation owner, and change directory to *Grid_home*.
2. Start the Oracle Grid Infrastructure configuration wizard:

```
$ ./gridSetup.sh
```

3. Provide information as needed for configuration. OUI validates the information and configures the installation on all cluster nodes.
4. When you complete providing information, OUI shows you the Summary page, listing the information you have provided for the cluster. Verify that the summary has the correct information for your cluster, and click **Install** to start configuration of the local node.

When configuration of the local node is complete, OUI copies the Oracle Grid Infrastructure configuration file to other cluster member nodes.

5. When prompted, run `root` scripts.
6. When you confirm that all `root` scripts are run, OUI checks the cluster configuration status, and starts other configuration tools as needed.

Configuring the Software Binaries Using a Response File

When you install or copy Oracle Grid Infrastructure software on any node, you can defer configuration for a later time. Review this procedure for completing configuration after the software is installed or copied on nodes, using the configuration wizard (`gridSetup.sh`).

To configure the Oracle Grid Infrastructure software binaries using a response file:

1. As the Oracle Grid Infrastructure installation owner (`grid`), start Oracle Universal Installer in Oracle Grid Infrastructure configuration wizard mode from the Oracle Grid Infrastructure software-only home using the following syntax, where *filename* is the response file name:

```
/u01/app/23.0.0/grid/gridSetup.sh [-debug] [-silent -responseFile filename]
```

For example:

```
$ cd /u01/app/23.0.0/grid
$ ./gridSetup.sh -responseFile /u01/app/23.0.0/grid/install/response/
response_file.rsp
```

2. When you complete configuring values, OUI shows you the Summary page, listing all information you have provided for the cluster. Verify that the summary has the correct information for your cluster, and click **Install** to start configuration of the local node.

When configuration of the local node is complete, OUI copies the Oracle Grid Infrastructure configuration file to other cluster member nodes.

3. When prompted, run `root` scripts.
4. When you confirm that all `root` scripts are run, OUI checks the cluster configuration status, and starts other configuration tools as needed.

Setting Ping Targets for Network Checks

Receive notification about network status by setting the `Ping_Targets` parameter during the Oracle Grid Infrastructure installation.

For environments where the network link status is not correctly returned when the network cable is disconnected, for example, in a virtual machine, you can receive notification about network status by setting the `Ping_Targets` parameter during the Oracle Grid Infrastructure installation.

Run the installer:

```
./gridSetup.sh oracle_install_crs_Ping_Targets=Host1|IP1,Host2|IP2
```

The ping utility contacts the comma-separated list of host names or IP addresses `Host1|IP1,Host2|IP2` to determine whether the public network is available. If none of the hosts respond, then the network is considered to be offline. Addresses outside the cluster, like of a switch or router, should be used.

For example:

```
/gridSetup.sh oracle_install_crs_Ping_Targets=192.0.2.1,192.0.2.2
```

About Deploying Oracle Grid Infrastructure Using Oracle Fleet Patching and Provisioning

Learn how you can use Oracle Fleet Patching and Provisioning (Oracle FPP) to provision your Oracle homes, and to manage your software lifecycle.

Note:

Starting with Oracle Grid Infrastructure 19c, the feature formerly known as Rapid Home Provisioning (RHP) is now Oracle Fleet Patching and Provisioning (Oracle FPP).

Oracle FPP is a software lifecycle management method for provisioning and maintaining Oracle homes. Oracle Fleet Patching and Provisioning enables mass deployment and maintenance of standard operating environments for databases, clusters, and user-defined software types.

Oracle Fleet Patching and Provisioning enables you to install clusters, and provision, patch, scale, and upgrade Oracle Grid Infrastructure, Oracle Restart, and Oracle Database homes. The supported releases are 12.2 and later releases. You can also provision applications and middleware using Oracle Fleet Patching and Provisioning.

Oracle Fleet Patching and Provisioning is a service in Oracle Grid Infrastructure that you can use in either of the following modes:

- Central Oracle Fleet Patching and Provisioning Server

The Oracle Fleet Patching and Provisioning Server stores and manages standardized images, called gold images. Gold images can be deployed to any number of nodes across

the data center. You can create new clusters and databases on the deployed homes and can use them to patch, upgrade, and scale existing installations.

The Oracle Fleet Patching and Provisioning Server can manage the following types of installations:

- Software homes on the cluster hosting the Oracle Fleet Patching and Provisioning Server itself.
- Oracle Fleet Patching and Provisioning Clients running Oracle Grid Infrastructure 12c Release 2 (12.2) and later releases.
- Installations running without Oracle Grid Infrastructure.

The Oracle Fleet Patching and Provisioning Server can provision new installations, and manage existing installations, without requiring any changes to the existing installations. The Oracle Fleet Patching and Provisioning Server can automatically share gold images among peer servers to support enterprises with geographically distributed data centers.

- **Oracle Fleet Patching and Provisioning Client**

The Oracle Fleet Patching and Provisioning Client can be managed from the Oracle Fleet Patching and Provisioning Server, or directly by executing commands on the client itself. The Oracle Fleet Patching and Provisioning Client is a service built into the Oracle Grid Infrastructure and is available in Oracle Grid Infrastructure 12c Release 2 (12.2) and later releases. The Oracle Fleet Patching and Provisioning Client can retrieve gold images from the Oracle Fleet Patching and Provisioning Server, upload new images based on the policy, and apply maintenance operations to itself.

Oracle Fleet Patching and Provisioning

Deploying Oracle software using Oracle Fleet Patching and Provisioning has the following advantages:

- Ensures standardization and enables high degrees of automation with gold images and managed lineage of deployed software.
- Minimizes downtime by deploying new homes as images (called gold images) out-of-place, without disrupting active databases or clusters.
- Simplifies maintenance by providing automations which are invoked with a simple, consistent API across database versions and deployment models.
- Reduces maintenance risk with built-in validations and a *dry run* mode to test the operations.
- Enables you to resume or restart the commands in the event of an unforeseen issue, reducing the risk of maintenance operations.
- Minimizes and often eliminates the impact of patching and upgrades, with features that include:
 - Zero-downtime database upgrade with fully automated upgrade, processed entirely within the deployment without requiring any extra nodes or external storage.
 - Adaptive management of database sessions and OJVM during rolling patching.
 - Options for management of consolidated deployments.
- The deployment and maintenance operations enable customizations to include environment-specific actions into the automated workflow.

Related Topics

- *Oracle Clusterware Administration and Deployment Guide*

Confirming Oracle Clusterware Function

After Oracle Grid Infrastructure installation, confirm that your Oracle Clusterware installation is installed and running correctly.

After installation, log in as `root`, and use the following command syntax to confirm that your Oracle Clusterware installation is installed and running correctly:

```
crsctl check cluster -all
```

For example:

```
$ crsctl check cluster -all

*****
node1:
CRS-4537: Cluster Ready Services is online
CRS-4529: Cluster Synchronization Services is online
CRS-4533: Event Manager is online
*****
node2:
CRS-4537: Cluster Ready Services is online
CRS-4529: Cluster Synchronization Services is online
CRS-4533: Event Manager is online
*****
node3:
CRS-4537: Cluster Ready Services is online
CRS-4529: Cluster Synchronization Services is online
CRS-4533: Event Manager is online
*****
```

Note:

After installation is complete, do not remove manually or run `cron` jobs that remove `/tmp/.oracle` or `/var/tmp/.oracle` or its files while Oracle Clusterware is up. If you remove these files, then Oracle Clusterware could encounter intermittent delays, and you will encounter error `CRS-0184: Cannot communicate with the CRS daemon`.

Confirming Oracle ASM Function for Oracle Clusterware Files


Confirm Oracle ASM is running after installing Oracle Grid Infrastructure.

After Oracle Grid Infrastructure installation, Oracle Clusterware files are stored on Oracle ASM. Use the following command syntax as the Oracle Grid Infrastructure installation owner (`grid`) to confirm that your Oracle ASM installation is running:

```
srvctl status asm
```

For example:

```
srvctl status asm  
ASM is running on node1,node2, node3, node4
```

 **Note:**

To manage Oracle ASM or Oracle Net, use the `srvctl` binary in the Oracle Grid Infrastructure home for a cluster (Grid home). If you have Oracle Real Application Clusters or Oracle Database installed, then you cannot use the `srvctl` binary in the database home to manage Oracle ASM or Oracle Net.

Understanding Offline Processes in Oracle Grid Infrastructure

After the installation of Oracle Grid Infrastructure, some components may be listed as OFFLINE. Oracle Grid Infrastructure activates these resources when you choose to add them.

Oracle Grid Infrastructure provides required resources for various Oracle products and components. Some of those products and components are optional, so you can install and enable them after installing Oracle Grid Infrastructure. To simplify postinstall additions, Oracle Grid Infrastructure preconfigures and registers all required resources for all products available for these products and components, but only activates them when you choose to add them. As a result, some components may be listed as OFFLINE after the installation of Oracle Grid Infrastructure. Run the following command to view status of any resource:

```
$ crsctl status resource resource_name -t
```

Resources listed as TARGET:OFFLINE and STATE:OFFLINE do not need to be monitored. They represent components that are registered, but not enabled, so they do not use any system resources. If an Oracle product or component is installed on the system, and it requires a particular resource to be online, then the software prompts you to activate the required offline resource.

10

Patching Oracle Grid Infrastructure

You can download and install Oracle Grid Infrastructure patches either as a complete gold image with pre-applied RUs or as individual software patches from My Oracle Support.

- [About Individual Oracle Grid Infrastructure Patches](#)
Download Oracle ASM individual (one-off) patch and apply it to Oracle Grid Infrastructure using the `setup.exe -applyOneOffs` command.
- [About Oracle Grid Infrastructure Software Patch Levels](#)
Review this topic to understand how to apply patches for Oracle ASM and Oracle Clusterware.
- [About Zero-Downtime Oracle Grid Infrastructure Patching](#)
Use the zero-downtime Oracle Grid Infrastructure patching method to keep your Oracle RAC database instances running and client connections active during patching.
- [Applying Patches to Oracle Grid Infrastructure](#)
Review these scenarios for applying patches to Oracle Grid Infrastructure in different stages of installation or upgrade.
- [Patching and Switching Oracle Grid Infrastructure Homes](#)
Use `switchGridHome` command to switch from the current Oracle Grid Infrastructure home to the patched Oracle Grid Infrastructure home.
- [Patching Oracle Grid Infrastructure Using Oracle FPP Local Mode](#)
Use this procedure to patch Oracle Grid Infrastructure using Oracle Fleet Patching and Provisioning (Oracle FPP) Local Mode.
- [Changing the Oracle Grid Infrastructure Base Path](#)
After installing Oracle Grid Infrastructure for a cluster (Oracle Clusterware and Oracle ASM configured for a cluster), you can change the Grid base path, if required.

About Individual Oracle Grid Infrastructure Patches

Download Oracle ASM individual (one-off) patch and apply it to Oracle Grid Infrastructure using the `setup.exe -applyOneOffs` command.

Individual patches are called **one-off** patches. An Oracle ASM one-off patch is available for a specific release of Oracle ASM. If a patch you want is available, then you can download the patch and apply it to Oracle ASM using the `setup.exe -applyOneOffs` command. The Oracle Clusterware inventory keeps track of the patches you have installed for your release of Oracle ASM. If there is a conflict between the patches you have installed and patches you want to apply, then Oracle Clusterware advises you of these conflicts.



Note:

The use of OPatch and OPatchAuto for out-of-place patching continues to be deprecated.

About Oracle Grid Infrastructure Software Patch Levels

Review this topic to understand how to apply patches for Oracle ASM and Oracle Clusterware.

The software patch level for Oracle Grid Infrastructure represents the set of all one-off patches and Release Updates (RUs) applied to the Oracle Grid Infrastructure software release, including Oracle ASM. The release is the release number, in the format of major and RU release number. For example, with the release number 23.5.0.0.0, the major release is 23 and the RU release number is 5. The RU release number changes for RU patches, but it does not change for one-off patches.

As with standard upgrades to Oracle Grid Infrastructure, at any given point in time for normal operation of the cluster, all the nodes in the cluster must have the same software release and patch level. Because one-off patches can be applied as rolling upgrades, all possible patch levels on a particular software release are compatible with each other.

About Zero-Downtime Oracle Grid Infrastructure Patching

Use the zero-downtime Oracle Grid Infrastructure patching method to keep your Oracle RAC database instances running and client connections active during patching.

Zero-downtime patching does not affect I/O for the Oracle Database storage. All instances of Oracle Advanced Cluster File System (Oracle ACFS) remain mounted and accessible during patching. The database listeners that are running from the Oracle Database homes are not affected, however, the listeners that are running from the Oracle Grid Infrastructure home restart while patching Oracle Grid Infrastructure.

You can use zero-downtime patching only for out-of-place patching of Oracle Grid Infrastructure 19c Release Update (RU) 19.8 or later releases with Oracle RAC or Oracle RAC One Node databases of 19c or later releases. If your Oracle RAC or Oracle RAC One Node database release is older than 19c, then the database instances stop during zero-downtime patching.

Note:

The success of zero-downtime patching depends on the availability of the system resources. If sufficient system resources are not available and if the patching software estimates that Oracle Grid Infrastructure will remain shut down for more than 15 seconds, then the patching software stops the patching process. In this case, you need to patch Oracle Grid Infrastructure when sufficient system resources are available.

Zero-Downtime Patching and Operating System Drivers

Zero-downtime patching does not automatically update the operating system drivers. During the zero-downtime patching process, updated operating system drivers are copied in the Grid home, but these drivers are not installed into the operating system. The cluster continues to use the older version of the operating system drivers until the updated drivers are installed in the operating system.

If you are using Oracle ASM Filter Driver (Oracle ASMFd) or Oracle ACFS for database storage, then operating system drivers are updated in either of the following scenarios:

1. You update your operating system kernel and restart the cluster node.

2. You run the `rootcrs.sh -updateosfiles` command on each cluster node and restart the cluster nodes, if the operating system drivers fail to install.

You can check the active operating system driver version on a cluster node using the `crsctl query driver activeversion [-all]` command and available operating system driver version using the `crsctl query driver softwareversion [-all] [-f]` command.

If the patch that you are installing contains operating system driver updates, then you must use the `-skipDriverUpdate` option during zero-downtime patching, else the patching process fails. The `-skipDriverUpdate` option does not affect the existing operating system driver, even if the Release Update (RU) contains driver updates.

After you apply the patches using zero-downtime patching, the active and available operating system driver versions are different until either of the above two scenarios is true.

Related Topics

- *Oracle Advanced Cluster File System Administrator's Guide*

Applying Patches to Oracle Grid Infrastructure

Review these scenarios for applying patches to Oracle Grid Infrastructure in different stages of installation or upgrade.

- [Applying Patches Using Zero-Downtime Oracle Grid Infrastructure Patching](#)
Oracle Grid Infrastructure enables you to keep your Oracle RAC database instances running and accessible to the database users during Oracle Grid Infrastructure patching.
- [Applying Patches During an Oracle Grid Infrastructure Installation or Upgrade](#)
You can download and apply Release Updates (RUs) and one-off patches during an Oracle Grid Infrastructure installation or upgrade.
- [Applying Patches After an Oracle Grid Infrastructure Installation or Upgrade](#)
You can apply patches to Oracle Grid Infrastructure deployment in rolling mode after a successful or a failed upgrade. This mode is similar to the "Rolling Upgrade" mode in terms of the Oracle ASM operations allowed in this quiesce state.
- [Applying Patches when Oracle Clusterware Fails to Start](#)
If the Oracle Clusterware stack does not start because of any error, then you can patch Oracle Grid Infrastructure using the OPatch utility.

Applying Patches Using Zero-Downtime Oracle Grid Infrastructure Patching

Oracle Grid Infrastructure enables you to keep your Oracle RAC database instances running and accessible to the database users during Oracle Grid Infrastructure patching.

Use the `switchGridHome` command to switch from the current Oracle Grid Infrastructure home to the patched Oracle Grid Infrastructure home. You can use the `switchGridHome` command only to switch between different RUs of the same release, for example from Oracle Grid Infrastructure 23.3 to Oracle Grid Infrastructure 23.4.

Note:

You can use zero-downtime patching only for out-of-place patching of Oracle Grid Infrastructure with Oracle RAC or Oracle RAC One Node databases of 19c or later releases. If your Oracle RAC or Oracle RAC One Node database release is older than 19c, then the database instances stop during zero-downtime patching.

1. Download the Oracle Database Release Updates (RUs) you want to apply from My Oracle Support.
2. As the `grid` user, download the Oracle Grid Infrastructure image files and extract the files into a new Oracle Grid Infrastructure home directory.

```
$ mkdir -p /u01/app/23.7.0/grid
$ chown grid:oinstall /u01/app/23.7.0/grid
$ cd /u01/app/23.7.0/grid
$ unzip -q download_location/grid.zip
```

 **Note:**

The new Oracle Grid Infrastructure home path must be different from the current Oracle Grid Infrastructure home path.

3. Switch to the patched Oracle Grid Infrastructure home using either of the following methods:
 - Start the Oracle Grid Infrastructure installer in interactive mode from the patched home.

```
$ /u01/app/23.7.0/grid/gridSetup.sh
```

Then perform the following steps:

- a. Select the **Patch Oracle Grid Infrastructure** option in the Configuration Option window.
 - b. Select the **Use Zero Downtime GI patching** option to switch to the patched Oracle Grid Infrastructure home.
 - c. Select the **Skip updating ACFS drivers** option if the patch that you are installing contains operating system driver updates and you want to skip them.
 - d. Respond to the installation screens with values appropriate for your environment.
- Start the Oracle Grid Infrastructure installer in silent mode, with the `-switchGridHome` flag, from the patched home.

```
$ /u01/app/23.7.0/grid/gridSetup.sh -silent -switchGridHome [-
zeroDowntimeGIPatching [-skipDriverUpdate]]
[-applyOneOffs comma_seperated_list_of_patch_directory_locations]
```

4. Follow the steps in the configuration wizard to complete the Oracle Grid Infrastructure installation.

All Oracle Grid Infrastructure services start running from the new Grid home after the patching is complete.

5. Verify that the patching has completed.

```
$ /u01/app/23.7.0/grid/crsctl query crs activeversion -f
Oracle Clusterware active version on the cluster is [23.0.0.0.0]. The
cluster upgrade state is [NORMAL].
The cluster active patch level is 456789126.
```

6. If the patching fails, then perform the following steps to rollback the patch:

- a. As the `root` user, run the prepatch script.

```
# /u01/app/23.7.0/grid/crs/install/rootcrs.sh -prepatch -dstcrshome  
Old_GI_Home  
-nodriverupdate -transparent -rollback
```

- b. As the `root` user, run the postpatch script.

```
# /u01/app/23.7.0/grid/crs/install/rootcrs.sh -postpatch -dstcrshome  
Old_GI_Home  
-nodriverupdate -transparent -rollback
```

7. If you have successfully switched to the new Grid home on all nodes and want to switch back to the old Grid home, then perform the following steps:

- a. As the `root` user, unlock the old Grid home on all the cluster nodes.

```
# Old_GI_Home/crs/install/rootcrs.sh -unlock -crshome Old_GI_Home
```

- b. As the `grid` user, run `switchGridHome` from the old Grid home.

```
$ Old_GI_Home/gridSetup.sh -silent -switchGridHome [-  
zeroDowntimeGIPatching [-skipDriverUpdate]]
```

Related Topics

- Zero-Downtime Grid Infrastructure Patching Using Oracle FPP

Applying Patches During an Oracle Grid Infrastructure Installation or Upgrade

You can download and apply Release Updates (RUs) and one-off patches during an Oracle Grid Infrastructure installation or upgrade.

1. Download the patches you want to apply from My Oracle Support:

<https://support.oracle.com>

2. Select the **Patches and Updates** tab to locate the patch.

Oracle recommends that you select **Recommended Patch Advisor**, and enter the product group, release, and platform for your software.

3. Move the patches to an accessible directory like `/tmp`.

4. Change to the Oracle Grid Infrastructure home directory:

```
$ cd /u01/app/23.0.0/grid
```

5. Apply Release Updates (RUs) and any one-off patches during the installation or upgrade process:

```
$ ./gridSetup.sh -applyRU /tmp/patch_ID -applyOneOffs /tmp/patch_ID
```


 **Note:**

You can apply RUs and one-off patches separately or together in the same command.

6. Complete the remaining steps in the Oracle Grid Infrastructure configuration wizard to complete the installation or upgrade.

Applying Patches After an Oracle Grid Infrastructure Installation or Upgrade

You can apply patches to Oracle Grid Infrastructure deployment in rolling mode after a successful or a failed upgrade. This mode is similar to the "Rolling Upgrade" mode in terms of the Oracle ASM operations allowed in this quiesce state.

1. Download patches you want to apply from My Oracle Support:

<https://support.oracle.com>

Select the **Patches and Updates** tab to locate the patch.

Oracle recommends that you select **Recommended Patch Advisor**, and enter the product group, release, and platform for your software. My Oracle Support provides you with a list of the most recent Release Updates (RUs) and Release Update Revisions (RURs).

Place the patches in an accessible directory, such as `/tmp`.

2. Review the patch documentation for the patch you want to apply, and complete all required steps before starting the patch upgrade.
3. Follow the instructions in the patch documentation to apply the patch on the first node.

```
# Grid_home/OPatch/opatchauto apply /tmp/patch_ID
```

Wait for the patching to finish on the first node before patching other cluster nodes.

 **Note:**

The use of OPatch and OPatchAuto for out-of-place patching continues to be deprecated.

For patching in Oracle Database 23ai, Oracle recommends that you use out-of-place patching using Gold images to apply quarterly release updates (RUs). This deprecation does not affect in-place patching. If you want to perform in-place patching, then OPatch and OPatchAuto continue to be available for this purpose. The Oracle Database 23ai Free release is not supported for patching with RUs.

4. Apply the patch on all other cluster nodes, one at a time.

```
# Grid_home/OPatch/opatchauto apply patch_directory_location/patch_ID
```

Applying Patches when Oracle Clusterware Fails to Start

If the Oracle Clusterware stack does not start because of any error, then you can patch Oracle Grid Infrastructure using the OPatch utility.

1. Download patches you want to apply from My Oracle Support:

<https://support.oracle.com>

Select the **Patches and Updates** tab to locate the patch.

Oracle recommends that you select **Recommended Patch Advisor**, and enter the product group, release, and platform for your software. My Oracle Support provides you with a list of the most recent Release Updates (RUs) and Release Update Revisions (RURs).

Place the patches in an accessible directory, such as `/tmp`.

2. Review the patch documentation for the patch you want to apply, and complete all required steps before starting the patch upgrade.
3. As the `root` user, stop the Oracle Clusterware stack on the first node.

```
# $ORACLE_HOME/bin/crsctl stop crs -f
```

4. Unlock the Oracle Grid Infrastructure home on the first node.

```
# $ORACLE_HOME/crs/install/rootcrs.sh -unlock
```

5. As the `grid` user, follow the instructions in the patch documentation to apply the patch on the first node.

```
$ $ORACLE_HOME/OPatch/patch apply patch_directory_location/patch_ID
```

Wait for the patching to finish on the first node before patching other cluster nodes.

6. As the `root` user, lock the Oracle Grid Infrastructure home on the first node.

```
# $ORACLE_HOME/rdbms/install/rootadd_rdbms.sh  
# $ORACLE_HOME/crs/install/rootcrs.sh -lock
```

7. Update Oracle Local Registry (OLR) to the patch level on the first node.

```
# $ORACLE_HOME/bin/clscfg -localpatch
```

8. Check if Oracle Clusterware is in the `ROLLING PATCH` mode.

```
$ crsctl query crs activeversion -f  
Oracle Clusterware active version on the cluster is [23.0.0.0.0].  
The cluster upgrade state is [NORMAL]. The cluster active patch level is  
[0].
```

If Oracle Clusterware is not in the `ROLLING PATCH` mode, then set Oracle Clusterware in `ROLLING PATCH` mode from a node where Oracle Clusterware is online.

```
$ crsctl start rollingpatch
```

9. Start the Oracle Clusterware stack on the first node.

```
# $ORACLE_HOME/bin/crsctl start crs
```

10. Update Oracle Cluster Registry (OCR) to the patch level on the first node.

```
# $ORACLE_HOME/bin/clscfg -patch
```

11. Repeat steps 3 through 10 on all other cluster nodes.

You can patch all other cluster nodes in parallel.

12. Transition Oracle Clusterware out of the `ROLLING PATCH` mode.

```
$ crsctl stop rollingpatch
```

Patching and Switching Oracle Grid Infrastructure Homes

Use `switchGridHome` command to switch from the current Oracle Grid Infrastructure home to the patched Oracle Grid Infrastructure home.

You can use the `switchGridHome` command to switch between different RUs of the same release, for example from Oracle Grid Infrastructure 23.6 to Oracle Grid Infrastructure 23.7. You can also use the `switchGridHome` command to apply one-off patches.

1. As the `grid` user, download the Oracle Grid Infrastructure image files and extract the files into a new Oracle Grid Infrastructure home directory.

```
$ mkdir -p /u01/app/23.7.0/grid
$ chown grid:oinstall /u01/app/23.7.0/grid
$ cd /u01/app/23.7.0/grid
$ unzip -q download_location/grid.zip
```

Note:

The new Oracle Grid Infrastructure home path must be different from the current Oracle Grid Infrastructure home path.

2. Download the Oracle Database RU version that you want to apply from My Oracle Support.
For more information, see, [Downloading Release Update Patches](#)
3. Perform the software only installation of the Oracle Grid Infrastructure using the Oracle Universal Installer.
4. Switch to the patched Oracle Grid Infrastructure home using one of the following methods:
 - Start the Oracle Grid Infrastructure installer in interactive mode from the patched home.

```
$ /u01/app/23.7.0/grid/gridSetup.sh
```

Then perform the following steps:

- a. Select the **Patch Oracle Grid Infrastructure** option in the Select Configuration Option window.
- b. Select the **Use Zero Downtime GI patching** option to switch to the patched Oracle Grid Infrastructure home.

- c. Select the **Do not update ACFS drivers** option if the patch that you are installing contains operating system driver updates and you want to skip them.
- d. Respond to the installation screens with values appropriate for your environment.
- Start the Oracle Grid Infrastructure installer in silent mode, with the `-switchGridHome` flag, from the patched home.

```
$ /u01/app/23.7.0/grid/gridSetup.sh -silent -switchGridHome [-zeroDowntimeGIPatching [-skipDriverUpdate]]
```

5. Follow the steps in the configuration wizard to complete the Oracle Grid Infrastructure installation.

All Oracle Grid Infrastructure services start running from the new Grid home after the installation is complete.

6. If the patching fails, then rollback the patch:

```
$ /u01/app/23.7.0/grid/gridSetup.sh -switchGridHome -rollback -silent -oldHome Old_GI_Home
```

7. If you have successfully switched to the new Grid home on all nodes and want to switch back to the old Grid home, then perform the following steps:

- a. As the `root` user, unlock the old Grid home on all the cluster nodes.

```
# Old_GI_Home/crs/install/rootcrs.sh -unlock -crshome Old_GI_Home
```

- b. As the `grid` user, run `switchGridHome` from the old Grid home.

```
$ Old_GI_Home/gridSetup.sh -silent -switchGridHome [-zeroDowntimeGIPatching [-skipDriverUpdate]]
```

Patching Oracle Grid Infrastructure Using Oracle FPP Local Mode

Use this procedure to patch Oracle Grid Infrastructure using Oracle Fleet Patching and Provisioning (Oracle FPP) Local Mode.

1. Deploy a new Oracle Grid Infrastructure home using Oracle FPP Local Mode.

```
$ rhpctl deploy home -path /u01/app/23.6.0/grid -zip /tmp/images/grid_home.zip
```

2. Switch from the old Oracle Grid Infrastructure home to the new Oracle Grid Infrastructure home using Oracle FPP Local Mode.

```
$ rhpctl move gihome -desthome /u01/app/23.6.0/grid -sourcehome /u01/app/23.0.0/grid
```

 **Note:**

- During Oracle FPP Local Mode patching, you must run the patching command only on one node. The patching completes automatically on all other nodes.
- If any command fails in the first run, then you must re-run the command from the same node where it was started initially.

Related Topics

- [rhpctl deploy home](#)
- [rhpctl move gihome](#)

Changing the Oracle Grid Infrastructure Base Path

After installing Oracle Grid Infrastructure for a cluster (Oracle Clusterware and Oracle ASM configured for a cluster), you can change the Grid base path, if required.

This procedure applies to Oracle Grid Infrastructure 19c Release Update (19.21) and later releases.

 **Note:**

Before changing the Grid base, you must shut down all executable that run in the Grid base directory that you are relinking. In addition, shut down applications linked with Oracle shared libraries.

1. As the `root` user, create a new Oracle base directory and change the owner and group for the directory and files in the new Grid base.

```
# mkdir -p /u02/app/grid
# chown -R grid:oinstall /u02/app/grid
```

2. Stop the Oracle Clusterware stack and TFA on all cluster nodes.

```
# $ORACLE_HOME/bin/crsctl stop crs
# tfactl stop
```

3. Copy the Oracle Grid Infrastructure files from the old Grid base location to the new Grid base location. For example, where the old Grid base is `/u01/app/grid` and the new Grid base is `/u02/app/grid`.

```
# cp -pR /u01/app/grid /u02/app/grid
```

4. Create a backup of the old Oracle base to ensure new files are not created.

```
# cp /u01/app/grid /u01/app/grid.old
```

5. Edit the `crsconfig_params` file using a text editor and update the `ORACLE_BASE` parameter to the new Oracle base on all cluster nodes.

```
ORACLE_BASE=/u02/app/grid
```

6. Edit the `orabasetab` file using a text editor and update the `ORACLE_BASE` parameter to the new Oracle base on all cluster nodes.

```
ORACLE_BASE=/u01/app/23.0.0/grid:/u02/app/grid:OraGI23Home1:N:
```

7. Edit the `/etc/oracle/olr.loc` file using a text editor and update the `olrconfig_loc` parameter with the new `ORACLE_BASE` path.

```
olrconfig_loc=/u02/app/grid/crsdata/$HOSTNAME/olr/$HOSTNAME_23.olr
```

8. Restore Oracle Grid Infrastructure home file permissions on all cluster nodes.

```
# /u01/app/23.0.0/grid/crs/install/rootcrs.sh -init
```

9. Move AHF data directory to the new Oracle base.

```
# ahfctl movedatadir /u02/app/grid
```

10. Start the Oracle Clusterware stack on all cluster nodes.

```
# $ORACLE_HOME/bin/crsctl start crs
```

11. Delete the old Oracle base directory.

```
# mv /u01/app/grid /u01/app/grid.old
```

12. Update the new Oracle base location in the `Grid_home/inventory/ContentsXML/oraclehomeproperties.xml` and `Grid_home/network/admin/sqlnet.ora` files.

13. Confirm if any logs or traces are created in the old Oracle base after this change.

```
# diff /u02/app/grid/diag/crs/node_name/crs/trace/ /u01/app/grid.old/diag/crs/node_name/crs/trace/
```

Upgrading Oracle Grid Infrastructure

Oracle Grid Infrastructure upgrade consists of upgrade of Oracle Clusterware and Oracle Automatic Storage Management (Oracle ASM).

Oracle Grid Infrastructure upgrades can be rolling upgrades, in which a subset of nodes are brought down and upgraded while other nodes remain active.

- [Understanding Out-of-Place Upgrade](#)
With an out-of-place upgrade, the installer installs the newer version in a separate Oracle Clusterware home.
- [About Oracle Grid Infrastructure Upgrade and Downgrade](#)
You have the ability to upgrade or downgrade Oracle Grid Infrastructure to a supported release.
- [Options for Oracle Grid Infrastructure Upgrades](#)
Review these upgrade options when you upgrade to Oracle Grid Infrastructure 23ai.
- [Restrictions for Oracle Grid Infrastructure Upgrades](#)
Restrictions and changes for upgrades to Oracle Clusterware installations, which consists of Oracle Grid Infrastructure and Oracle Automatic Storage Management (Oracle ASM).
- [Preparing to Upgrade an Existing Oracle Clusterware Installation](#)
If you have an existing Oracle Clusterware installation, then you upgrade your existing cluster by performing an out-of-place upgrade. You cannot perform an in-place upgrade.
- [Understanding Rolling Upgrades Using Batches](#)
You can perform rolling upgrades of Oracle Grid Infrastructure in batches.
- [Performing Rolling Upgrade of Oracle Grid Infrastructure](#)
Review this information to perform rolling upgrade of Oracle Grid Infrastructure.
- [About Upgrading Oracle Grid Infrastructure Using Oracle Fleet Patching and Provisioning](#)
Oracle Fleet Patching and Provisioning (Oracle FPP) is a software lifecycle management method for provisioning and patching Oracle homes.
- [Updating Oracle Enterprise Manager Cloud Control Target Parameters](#)
After upgrading Oracle Grid Infrastructure, upgrade the Enterprise Manager Cloud Control target.
- [Unlocking and Deinstalling the Previous Release Grid Home](#)
After upgrading from previous releases, if you want to deinstall the previous release Oracle Grid Infrastructure home, then you must first change the permission and ownership of the previous release Grid home.
- [Checking Cluster Health Monitor Repository Size After Upgrading](#)
If you are upgrading Oracle Grid Infrastructure from a prior release using IPD/OS to the current release, then review the Cluster Health Monitor repository size (the CHM repository).
- [Downgrading Oracle Clusterware to an Earlier Release](#)
After a successful or a failed upgrade, you can downgrade Oracle Clusterware to the previous release.

- [Completing Failed or Interrupted Installations and Upgrades](#)
If Oracle Universal Installer (OUI) exits on the node from which you started the upgrade, or the node reboots before you confirm that the `rootupgrade.sh` script was run on all nodes, then the upgrade remains incomplete.

Related Topics

- [About Upgrading Oracle Grid Infrastructure Using Oracle Fleet Patching and Provisioning](#)
Oracle Fleet Patching and Provisioning (Oracle FPP) is a software lifecycle management method for provisioning and patching Oracle homes.

Understanding Out-of-Place Upgrade

With an out-of-place upgrade, the installer installs the newer version in a separate Oracle Clusterware home.

Rolling upgrade avoids downtime and ensure continuous availability while the software is upgraded to a new version. Both versions of Oracle Clusterware are on each cluster member node, but only one version is active.

If you have separate Oracle Clusterware homes on each node, then you can perform an out-of-place upgrade on all nodes, or perform an out-of-place rolling upgrade, so that some nodes are running Oracle Clusterware from the earlier version Oracle Clusterware home, and other nodes are running Oracle Clusterware from the new Oracle Clusterware home.

An in-place upgrade of Oracle Grid Infrastructure is not supported.

About Oracle Grid Infrastructure Upgrade and Downgrade

You have the ability to upgrade or downgrade Oracle Grid Infrastructure to a supported release.

You can upgrade Oracle Grid Infrastructure in any of the following ways:

- Rolling Upgrade which involves upgrading individual nodes without stopping Oracle Grid Infrastructure on other nodes in the cluster.
- Non-rolling Upgrade which involves bringing down all the nodes except one. A complete cluster outage occurs while the root script stops the old Oracle Clusterware stack and starts the new Oracle Clusterware stack on the node where you initiate the upgrade. After upgrade is completed, the new Oracle Clusterware is started on all the nodes.

Note that some services are disabled when one or more nodes are in the process of being upgraded. All upgrades are out-of-place upgrades, meaning that the software binaries are placed in a different Grid home from the Grid home used for the prior release.

You can downgrade from Oracle Grid Infrastructure 23ai to Oracle Grid Infrastructure 21c and Oracle Grid Infrastructure 19c. Be aware that if you downgrade to a prior release, then your cluster must conform with the configuration requirements for that prior release, and the features available for the cluster consist only of the features available for that prior release of Oracle Clusterware and Oracle ASM.

You can perform out-of-place upgrades to an Oracle ASM instance using Oracle ASM Configuration Assistant (ASMCA). In addition to running ASMCA using the graphical user interface, you can run ASMCA in non-interactive (silent) mode.

 **Note:**

You must complete an upgrade before attempting to use cluster backup files. You cannot use backups for a cluster that has not completed upgrade.

 **See Also:**

Oracle Database Upgrade Guide and *Oracle Automatic Storage Management Administrator's Guide* for additional information about upgrading existing Oracle ASM installations

Options for Oracle Grid Infrastructure Upgrades

Review these upgrade options when you upgrade to Oracle Grid Infrastructure 23ai.

Supported upgrade paths for Oracle Grid Infrastructure for this release are:

- Oracle Grid Infrastructure upgrade from 19c release to Oracle Grid Infrastructure 23ai.
- Oracle Grid Infrastructure upgrade from 21c release to Oracle Grid Infrastructure 23ai.

Upgrade options from Oracle Grid Infrastructure 19c, and Oracle Grid Infrastructure 21c to Oracle Grid Infrastructure 23ai include the following:

- Oracle Grid Infrastructure rolling upgrade which involves upgrading individual nodes without stopping Oracle Grid Infrastructure on other nodes in the cluster
- Oracle Grid Infrastructure non-rolling upgrade by bringing the cluster down and upgrading the complete cluster

Restrictions for Oracle Grid Infrastructure Upgrades

Restrictions and changes for upgrades to Oracle Clusterware installations, which consists of Oracle Grid Infrastructure and Oracle Automatic Storage Management (Oracle ASM).

- Oracle Grid Infrastructure upgrades are always out-of-place upgrades. You cannot perform an in-place upgrade of Oracle Grid Infrastructure to existing homes.
- The same user who owned the earlier release Oracle Grid Infrastructure software must perform the Oracle Grid Infrastructure 23ai upgrade.
- Remove the Grid Infrastructure Management Repository (GIMR) from the existing Oracle Grid Infrastructure installation before the upgrade, if it was configured in the earlier release. The GIMR is desupported in Oracle Database 23ai.

Refer to [Removing Grid Infrastructure Management Repository](#) for steps to remove GIMR.

- Oracle ASM and Oracle Clusterware both run in the Oracle Grid Infrastructure home.
- Do not delete directories in the Grid home. For example, do not delete the directory `Grid_home/OPatch`. If you delete the directory, then the Grid infrastructure installation owner cannot use OPatch utility to patch the grid home, and OPatch displays the error message "'checkdir' error: cannot create `Grid_home/OPatch`".

- To upgrade existing Oracle Grid Infrastructure installations to Oracle Grid Infrastructure 23ai, you must first verify if you need to apply any mandatory patches for upgrade to succeed.

Oracle recommends that you use the Configuration Verification Utility (CVU) to check if there are any patches required for upgrading your existing Oracle Grid Infrastructure or Oracle RAC database installations. See *Using CVU to Validate Readiness for Oracle Clusterware Upgrades* for steps to check readiness.

- The software in the 23ai Oracle Grid Infrastructure home is not fully functional until the upgrade is completed. Running `srvctl`, `crsctl`, and other commands from the new Grid homes are not supported until the final `rootupgrade.sh` script is run and the upgrade is complete across all nodes.

To manage databases in existing earlier release database homes during the Oracle Grid Infrastructure upgrade, use the `srvctl` from the existing database homes.

See Also:

Oracle Database Upgrade Guide for additional information about preparing for upgrades

About Storage Restrictions for Upgrade

- If the Oracle Cluster Registry (OCR) and voting file locations for your current installation are on raw or block devices, then you must migrate them to an Oracle ASM disk group, certified NAS device, or a shared file system before upgrading to Oracle Grid Infrastructure 23ai.

About Upgrading Shared Grid Homes

- If the existing Oracle Clusterware home is a shared home, then you can use a non-shared home for the Oracle Grid Infrastructure for a cluster home for Oracle Clusterware and Oracle ASM 23ai.
- You can perform upgrades on a shared Oracle Clusterware home.

About Single-Instance Oracle ASM Upgrade

- During Oracle Grid Infrastructure installation or upgrade, if there is a single instance Oracle ASM release on the local node, then it is converted to an Oracle Flex ASM 23ai installation, and Oracle ASM runs in the Oracle Grid Infrastructure home on all nodes.
- If a single instance (non-clustered) Oracle ASM installation is on a remote node, which is a node other than the local node (the node on which the Oracle Grid Infrastructure installation or upgrade is being performed), then it remains a single instance Oracle ASM installation. However, during the installation or upgrade, when the OCR and voting files are placed on Oracle ASM, then an Oracle Flex ASM installation is created on all nodes in the cluster. The single instance Oracle ASM installation on the remote node becomes nonfunctional.

Related Topics

- [Using CVU to Validate Readiness for Oracle Clusterware Upgrades](#)
Oracle recommends that you use Configuration Verification Utility (CVU) to help to ensure that your upgrade is successful.

Preparing to Upgrade an Existing Oracle Clusterware Installation

If you have an existing Oracle Clusterware installation, then you upgrade your existing cluster by performing an out-of-place upgrade. You cannot perform an in-place upgrade.

The following topics list the steps you can perform before you upgrade Oracle Grid Infrastructure:

- [Upgrade Checklist for Oracle Grid Infrastructure](#)
 Review this checklist before upgrading an existing Oracle Grid Infrastructure. A cluster is being upgraded until all cluster member nodes are running the new installations, and the new clusterware becomes the active version.
- [Checks to Complete Before Upgrading Oracle Grid Infrastructure](#)
 Complete the following tasks before upgrading Oracle Grid Infrastructure.
- [Removing Grid Infrastructure Management Repository](#)
 GIMR is desupported in Oracle Database 23ai. If GIMR is configured in your existing Oracle Grid Infrastructure installation, then remove the GIMR.
- [Moving Oracle Clusterware Files from NFS to Oracle ASM](#)
 You can move Oracle Cluster Registry (OCR) and voting files from Network File System (NFS) to Oracle Automatic Storage Management (Oracle ASM) disk groups.
- [Running the Oracle ORAchk Upgrade Readiness Assessment](#)
 Download and run the Oracle ORAchk Upgrade Readiness Assessment before upgrading Oracle Grid Infrastructure.
- [Using CVU to Validate Readiness for Oracle Clusterware Upgrades](#)
 Oracle recommends that you use Configuration Verification Utility (CVU) to help to ensure that your upgrade is successful.
- [Using Dry-Run Upgrade Mode to Check System Upgrade Readiness](#)
 Use dry-run upgrade mode of Oracle Grid Infrastructure installation wizard, `gridSetup.sh`, to check readiness for Oracle Clusterware upgrades.


Upgrade Checklist for Oracle Grid Infrastructure

Review this checklist before upgrading an existing Oracle Grid Infrastructure. A cluster is being upgraded until all cluster member nodes are running the new installations, and the new clusterware becomes the active version.

Table 11-1 Upgrade Checklist for Oracle Grid Infrastructure Installation

Check	Task
Review Upgrade Guide for deprecation and desupport information that may affect upgrade planning.	<i>Oracle Database Upgrade Guide</i>
Patch set (recommended)	Install the latest patch set release for your existing installation. Review My Oracle Support note 2180188.1 for the list of latest patches before upgrading Oracle Grid Infrastructure.
Install user account	Confirm that the installation owner you plan to use is the same as the installation owner that owns the installation you want to upgrade.
Create a Grid home	Create a new Oracle Grid Infrastructure Oracle home (Grid home) where you can extract the image files. All Oracle Grid Infrastructure upgrades (upgrades of existing Oracle Clusterware and Oracle ASM installations) are out-of-place upgrades.

Table 11-1 (Cont.) Upgrade Checklist for Oracle Grid Infrastructure Installation

Check	Task
Remove the GIMR	<p>If the Grid Infrastructure Management Repository (GIMR) was configured in the earlier release, then remove GIMR from the existing Oracle Grid Infrastructure installation. Run the <code>\$Grid_home/crs/install/reposScript.sh -mode="Delete"</code> script from the new Oracle Grid Infrastructure home.</p> <p>If Oracle FPP Server was configured in the earlier release, then export the metadata using the <code>\$Grid_home/crs/install/reposScript.sh -mode="Export"</code> script.</p>
Operating System	Confirm that you are using a supported operating system, kernel release, and all required operating system packages for the new Oracle Grid Infrastructure installation.
OCR on raw or block devices	<p>Migrate OCR files from RAW or Block devices to Oracle ASM or a supported file system. Direct use of RAW and Block devices is not supported.</p> <p>Run the <code>ocrcheck</code> command to confirm Oracle Cluster Registry (OCR) file integrity. If this check fails, then repair the OCR before proceeding.</p>
Oracle ASM password file	<p>Move the Oracle ASM password file from file system to Oracle ASM, before proceeding with the upgrade using the following ASMCMD command:</p> <pre>ASMCMD [+] > pwcopy --asm current_location_of_ASM_password_file_in_OS_directory +target_disk_group_name/orapwASM</pre>
<div style="border-left: 2px solid #0070C0; padding-left: 10px; margin: 10px 0;">  Note: Set <code>compatible.asm</code> to at least 19.0.0.0, before moving the password file. </div>	
CVU Upgrade Validation	Use Configuration Verification Utility (CVU) to assist you with system checks in preparation for starting an upgrade.
Shut Down Single-instance Database	If you have a single-instance database on a cluster that uses Oracle ASM, then you must shut down the single-instance database before upgrading.
Unset Environment variables	<p>As the user performing the upgrade, unset the environment variables <code>\$ORACLE_HOME</code> and <code>\$ORACLE_SID</code>.</p> <p>Check that the <code>\$ORA_CRS_HOME</code> environment variable is not set. Do not use <code>\$ORA_CRS_HOME</code> as an environment variable, except under explicit direction from Oracle Support.</p> <p>Refer to the <i>Checks to Complete Before Upgrading Oracle Grid Infrastructure</i> for a complete list of environment variables to unset.</p>
Check system upgrade readiness with dry-run upgrade	Run Oracle Grid Infrastructure installation wizard, <code>gridSetup.sh</code> , in dry-run upgrade mode to perform system readiness checks for Oracle Grid Infrastructure upgrades.
Back Up the Oracle software before upgrades	Before you make any changes to the Oracle software, Oracle recommends that you create a backup of the Oracle software and databases.
HugePages memory allocation	Allocate memory to HugePages large enough for the System Global Areas (SGA) of all databases planned to run on the cluster.

Related Topics

- [Checks to Complete Before Upgrading Oracle Grid Infrastructure](#)
Complete the following tasks before upgrading Oracle Grid Infrastructure.

- [Oracle Clusterware Storage Space Requirements](#)
Use this information to determine the minimum number of disks and the minimum disk space requirements based on the redundancy type, for installing Oracle Clusterware files for various Oracle Cluster deployments.

Related Topics

- [Moving Oracle Clusterware Files from NFS to Oracle ASM](#)
You can move Oracle Cluster Registry (OCR) and voting files from Network File System (NFS) to Oracle Automatic Storage Management (Oracle ASM) disk groups.

Checks to Complete Before Upgrading Oracle Grid Infrastructure

Complete the following tasks before upgrading Oracle Grid Infrastructure.

1. For each node, use Configuration Verification Utility to ensure that you have completed preinstallation steps. It can generate Fixup scripts to help you to prepare servers. In addition, the installer helps you to ensure all required prerequisites are met.

Ensure that you have the information you need during installation, including the following:

- An Oracle base location for Oracle Clusterware.
 - An Oracle Grid Infrastructure home location that is different from your existing Oracle Clusterware location.
 - SCAN name and addresses, and other network addresses.
 - Privileged user operating system groups.
 - `root` user access, to run scripts as `root` during installation.
2. For the installation owner running the installation, if you have environment variables set for the existing installation, then unset the environment variables `$ORACLE_HOME` and `$ORACLE_SID`, as these environment variables are used during upgrade. For example, as the `grid` user, run the following commands on the local node:

For bash shell:

```
$ unset ORACLE_BASE
$ unset ORACLE_HOME
$ unset ORACLE_SID
```

For C shell:

```
$ unsetenv ORACLE_BASE
$ unsetenv ORACLE_HOME
$ unsetenv ORACLE_SID
```

3. If you have set `ORA_CRS_HOME` as an environment variable, following instructions from Oracle Support, then unset it before starting an installation or upgrade. You should never use `ORA_CRS_HOME` as an environment variable except under explicit direction from Oracle Support.
4. Ensure that the user profile for the installation user, for example, `.profile` or `.cshrc`, does not set any of these environment variables.
5. If you have an existing installation on your system, and you are using the same user account to install this installation, then unset the following environment variables: `ORA_CRS_HOME`, `ORACLE_HOME`, `ORA_NLS10`, `TNS_ADMIN` and any other environment variable set for the Oracle installation user who is connected with Oracle software homes.

6. Ensure that the `$ORACLE_HOME/bin` path is removed from your `PATH` environment variable.

Related Topics

- [Configuring Users, Groups and Environments for Oracle Grid Infrastructure and Oracle Database](#)
Before installation, create operating system groups and users, and configure user environments.
- [Configuring Networks for Oracle Grid Infrastructure and Oracle RAC](#)
Check that you have the networking hardware and internet protocol (IP) addresses required for an Oracle Grid Infrastructure for a cluster installation.

Removing Grid Infrastructure Management Repository

GIMR is desupported in Oracle Database 23ai. If GIMR is configured in your existing Oracle Grid Infrastructure installation, then remove the GIMR.

1. Confirm if Grid Infrastructure Management Repository (GIMR) is configured in the current release.

```
srvctl config mgmtdb
```

Note:

If GIMR is not configured, then do not follow this procedure.

2. Confirm if Oracle Fleet Patching and Provisioning (Oracle FPP) is configured in central server mode in the current release.

```
srvctl config rhpserver
```

Note:

If Oracle FPP is configured on your cluster, then you are recommended to use the Oracle FPP Self-Upgrade feature for smooth migration of the metadata from GIMR to the new metadata repository. Refer to Oracle Fleet Patching and Provisioning Self Upgrade for more information about how to use the Oracle FPP Self-Upgrade feature.

3. As the `grid` user, log in to any cluster node and create a new directory owned by `grid` to store the GIMR deletion script.

```
mkdir -p $ORACLE_HOME/gimrdel  
chown grid:oinstall $ORACLE_HOME/gimrdel
```

4. Download `scriptgimr.zip` from the My Oracle Support Note 2972418.1 to the `$ORACLE_HOME/gimrdel` directory.

5. Extract the `reposScript.sh` script from the `scriptgimr.zip` and ensure that the `grid` user has read and execute permissions on the `reposScript.sh` script.

```
unzip -q $ORACLE_HOME/gimrdel/scriptgimr.zip
```

6. Optional: Query and export the CHA user models.

```
Grid_home/bin/chactl query model
Grid_home/bin/chactl export model -name model_name -file model_name.svm
```

7. If Oracle FPP was configured in central mode, then export the Oracle FPP Metadata to re-configure Oracle FPP after upgrading to Oracle Grid Infrastructure 23ai.

```
Grid_home/crs/install/reposScript.sh -
export_dir=dir_to_export_Oracle_FPP_metadata
```

8. Run the `reposScript.sh` script, in delete mode, from the `/gimrdel` directory.

```
$ORACLE_HOME/gimrdel/reposScript.sh -mode="Delete"
```

Note:

Oracle FPP stops working if you delete the GIMR, but do not upgrade to Oracle Grid Infrastructure 23ai and re-configure Oracle FPP.

Related Topics

- [My Oracle Support Note 2972418.1](#)

Moving Oracle Clusterware Files from NFS to Oracle ASM

You can move Oracle Cluster Registry (OCR) and voting files from Network File System (NFS) to Oracle Automatic Storage Management (Oracle ASM) disk groups.

1. As the `grid` user, create the Oracle ASM disk group using ASMCA.

```
$ ./asmca
```

Follow the steps in the ASMCA wizard to create the Oracle ASM disk group, for example, DATA.

2. Move the voting files to the Oracle ASM disk group you created:

```
$ crsctl replace votedisk +DATA
```

The output of this command is as follows:

```
CRS-4256: Updating the profile
Successful addition of voting disk 24c6d682874a4f1ebf54f5ab0098b9e4.
Successful deletion of voting disk 1b5044fa39684f86bfbe681f388e55fb.
Successfully replaced voting disk group with +DATA_DG_OCR_VDSK.
```

```
CRS-4256: Updating the profile
CRS-4266: Voting file(s) successfully replaced
```

3. Check the status of Oracle Cluster Registry (OCR):

```
$ ./ocrcheck
```

The output of the command is as follows:

```
Status of Oracle Cluster Registry is as follows :
  Version                :          4
  Total space (kbytes)   :    409568
  Used space (kbytes)    :      1380
  Available space (kbytes) :    408188
  ID                     :    288871063
  Device/File Name       : /oradbocfs/storage/12101/ocr
  Device/File integrity check succeeded
  Cluster registry integrity check succeeded
```

4. As the `root` user, move the OCR files to the Oracle ASM disk group you created:

```
# ./ocrconfig -add +DATA
```

5. Delete the Oracle Clusterware files from the NFS location:

```
# ./ocrconfig -delete ocr_file_path_previously_on_nfs
```

Running the Oracle ORAchk Upgrade Readiness Assessment

Download and run the Oracle ORAchk Upgrade Readiness Assessment before upgrading Oracle Grid Infrastructure.

Oracle ORAchk is an Oracle RAC configuration audit tool. Oracle ORAchk Upgrade Readiness Assessment can be used to obtain an automated upgrade-specific health check for upgrades to Oracle Grid Infrastructure 19c, 21c, and 23ai. You can run the Oracle ORAchk Upgrade Readiness Assessment tool and automate many of the manual pre-upgrade and post-upgrade checks.

Oracle recommends that you download and run the latest version of Oracle ORAchk from My Oracle Support. For information about downloading, configuring, and running Oracle ORAchk, refer to My Oracle Support note 1457357.1.

Related Topics

- *Oracle Orachk and Exachk User's Guide*
- [My Oracle Support Note 1457357.1](#)

Using CVU to Validate Readiness for Oracle Clusterware Upgrades

Oracle recommends that you use Configuration Verification Utility (CVU) to help to ensure that your upgrade is successful.

 **Note:**

Starting with Oracle Grid Infrastructure 23ai, Cluster Verification Utility (CVU) is renamed to Configuration Verification Utility (CVU).

You can use CVU to assist you with system checks in preparation for starting an upgrade. CVU runs the appropriate system checks automatically, and either prompts you to fix problems, or provides a fixup script to be run on all nodes in the cluster before proceeding with the upgrade.

- [About the CVU Upgrade Validation Command Options](#)
Review this information about running upgrade validations.
- [Standalone CVU Home](#)
Starting with Oracle Database 23ai, you can use the Configuration Verification Utility (CVU) from a standalone alternative pluggable home during Oracle Grid Infrastructure installation or upgrade.
- [Example of Verifying System Upgrade Readiness for Grid Infrastructure](#)
You can verify that the permissions required for installing Oracle Clusterware have been configured on the nodes `node1` and `node2` by running a command similar to the following.

About the CVU Upgrade Validation Command Options

Review this information about running upgrade validations.

About Configuration Verification Utility (CVU)

- Run Oracle Universal Installer (OUI), and allow the Configuration Verification Utility (CVU) validation built into OUI to perform system checks and generate fixup scripts.
- Run the CVU manual script `cluvfy.sh` to perform system checks and generate fixup scripts.

To use OUI to perform pre-install checks and generate fixup scripts, run the installation as you normally would. OUI starts CVU, and performs system checks as part of the installation process. Selecting OUI to perform these checks is particularly appropriate if you think you have completed preinstallation checks, and you want to confirm that your system configuration meets minimum requirements for installation.

To use the `cluvfy.sh` command-line script for CVU, navigate to the new Grid home where you extracted the image files for upgrade, that contains the `runcluvfy.sh` script, and run the command `runcluvfy.sh stage -pre crsinst -upgrade` to check the readiness of your Oracle Clusterware installation for upgrades. Running `runcluvfy.sh` with the `-pre crsinst -upgrade` options performs system checks to confirm if the cluster is in a correct state for upgrading from an existing clusterware installation.

Syntax

The command uses the following syntax, where variable content is indicated by italics:

```
runcluvfy.sh stage -pre crsinst -upgrade [-rolling]
-src_crshome src_Gridhome ]-dest_crshome dest_Gridhome -dest_version
dest_release
[-fixup][-fixupnoexec][-method sudo -user user_name [-location dir_path][-
method root][-verbose]
```

Options

The options are:

- `-rolling`
Use this option to verify readiness for rolling upgrades.
- `-src_crshome src_Gridhome`
Use this option to indicate the location of the source Oracle Clusterware or Grid home that you are upgrading, where `src_Gridhome` is the path to the home that you want to upgrade.
- `-dest_crshome dest_Gridhome`
Use this option to indicate the location of the upgrade Grid home, where `dest_Gridhome` is the path to the Grid home.
- `-dest_version dest_release`
Use the `-dest_version` option to indicate the release number of the upgrade, including any patchset. The release number must include the five digits designating the release to the level of the platform-specific patch. For example: 23.0.0.0.0.
- `-fixup [-method sudo -user user_name [-location dir_path] [-method root]]`
Use the `-fixup` option to indicate that you want to generate instructions for any required steps you need to complete to ensure that your cluster is ready for an upgrade. The default location is the CVU work directory.

The `-fixup -method` option defines the method by which `root` scripts are run. The `-method` flag requires one of the following options:
 - `sudo`: Run as a user on the sudoers list.
 - `root`: Run as the `root` user.
 If you select `sudo`, then enter the `-location` option to provide the path to Sudo on the server, and enter the `-user` option to provide the user account with Sudo privileges.
- `-fixupnoexec`
If the option is specified, then on verification failure, the fix up data is generated and the instruction for manual execution of the generated fix ups is displayed.
- `-verbose`
Use the `-verbose` flag to produce detailed output of individual checks.

Standalone CVU Home

Starting with Oracle Database 23ai, you can use the Configuration Verification Utility (CVU) from a standalone alternative pluggable home during Oracle Grid Infrastructure installation or upgrade.

Standalone CVU home feature offers an alternative CVU software location that you can use to perform the prerequisite checks for Oracle Grid Infrastructure installation and upgrade. Oracle releases CVU standalone package quarterly, which you can download from the Oracle Technology Network website. Standalone CVU release is based on the latest Oracle Grid Infrastructure Release Update (RU) with critical fixes that you can use to verify Oracle Grid Infrastructure environment.

Follow these steps to use Standalone CVU for verification:

1. As the `grid` user, create a new standalone CVU home directory.

```
mkdir -p /u01/app/23.0.0/grid/cvuhome
```

 **Note:**

Ensure that the standalone CVU home directory has at least 500 MB free disk.

2. Download the `cvupack.zip` file from the Oracle Technology Network website to the standalone CVU home directory.
3. Unzip the `cvupack.zip` file in the standalone CVU home directory.
4. Launch Oracle Grid Infrastructure with the standalone CVU binaries.

```
/u01/app/23.0.0/grid/gridSetup.sh -DORA_CVU_LOC=/u01/app/23.0.0/grid/cvuhome
```

Example of Verifying System Upgrade Readiness for Grid Infrastructure

You can verify that the permissions required for installing Oracle Clusterware have been configured on the nodes `node1` and `node2` by running a command similar to the following.

Example 11-1 Running `runcluvfy` Command

```
$ /u01/app/23.0.0/grid/runcluvfy.sh stage -pre crsinst -upgrade -rolling -src_crshome /u01/app/19.0.0/grid -dest_crshome /u01/app/23.0.0/grid -dest_version 23.0.0.0.0 -fixup -verbose
```

Related Topics

- [Oracle Database Upgrade Guide](#)

Using Dry-Run Upgrade Mode to Check System Upgrade Readiness

Use dry-run upgrade mode of Oracle Grid Infrastructure installation wizard, `gridSetup.sh`, to check readiness for Oracle Clusterware upgrades.

- [About Oracle Grid Infrastructure Dry-Run Upgrade Mode](#)
Oracle Grid Infrastructure dry-run upgrade mode enables you to check system readiness for upgrade.
- [Performing Dry-Run Upgrade Using Oracle Universal Installer](#)
Run the Oracle Grid Infrastructure installer in dry-run upgrade mode to determine if the system is ready for upgrade.

About Oracle Grid Infrastructure Dry-Run Upgrade Mode

Oracle Grid Infrastructure dry-run upgrade mode enables you to check system readiness for upgrade.

Starting with Oracle Grid Infrastructure 19c, the Oracle Grid Infrastructure installer enables you to perform a dry-run upgrade to check readiness of the system for upgrade. To perform Oracle

Grid Infrastructure dry-run upgrade, create a new Grid home with the necessary user group permissions, extract the Oracle Grid Infrastructure 23ai gold image to the new Grid home, and then start the installer with `-dryRunForUpgrade` flag.

Dry-run upgrades are not supported on Oracle Grid Infrastructure for a standalone server (Oracle Restart) configurations.

 **Note:**

The installer does not perform an actual upgrade in the dry-run upgrade mode. You can relaunch the installer, without any flag, from any of the cluster nodes to upgrade Oracle Grid Infrastructure if dry-run is successful.

The installer performs the following tasks in dry-run upgrade mode:

- Validates storage and network configuration for the new release
- Checks if the system meets the software and hardware requirements for the new release
- Checks for the patch requirements and apply necessary patches before starting the upgrade
- Writes system configuration issues or errors in the `gridSetupActions<timestamp>.log` log file

The Grid infrastructure dry-run upgrade flow is similar to a regular upgrade, but the installer does not run any configuration tool.

Related Topics

- [Performing Dry-Run Upgrade Using Oracle Universal Installer](#)
Run the Oracle Grid Infrastructure installer in dry-run upgrade mode to determine if the system is ready for upgrade.

Performing Dry-Run Upgrade Using Oracle Universal Installer

Run the Oracle Grid Infrastructure installer in dry-run upgrade mode to determine if the system is ready for upgrade.

At any time during the dry-run upgrade, if you have a question about what you are being asked to do, or what input you are required to provide during dry-run upgrade, click the **Help** button on the installer page.

You should have your network information, storage information, and operating system users and groups available to you before you start dry-run upgrade.

1. As the `grid` user, download the Oracle Grid Infrastructure image file and extract the file to the Grid home.

For example:

```
$ mkdir -p /u01/app/23.0.0/grid
$ chown grid:oinstall /u01/app/23.0.0/grid
$ cd /u01/app/23.0.0/grid
$ unzip -q download_location/grid_home.zip
```

`download_location/grid_home.zip` is the path of the downloaded Oracle Grid Infrastructure image file.

 **Note:**

You must extract the image file into the directory where you want your Grid home to be located.

2. Start the Oracle Grid Infrastructure installation wizard in dry-run upgrade mode.

```
$ /u01/app/23.0.0/grid/gridSetup.sh -dryRunForUpgrade
```

3. Select **Upgrade Oracle Grid Infrastructure** option to perform dry-run upgrade for Oracle Grid Infrastructure (Oracle Clusterware and Oracle ASM).
4. Select installation options as prompted. Oracle recommends that you configure `root` script automation, so that the `rootupgrade.sh` script can be run automatically during the dry-run upgrade.
5. Run the `root` scripts, either automatically or manually:
 - **Running root scripts automatically:**
If you have configured `root` script automation, then the installer will run the `rootupgrade.sh` script automatically on the local node.
 - **Running root scripts manually**
If you have not configured `root` script automation, then when prompted, run the `rootupgrade.sh` script on the local node.

If you run the `root` scripts manually, then run the script only on the local node.

6. Check the `gridSetupActions<timestamp>.log` log file for errors and fix errors reported in the log file.
7. Exit the installer on the **Finish** screen.

 **Note:**

The `gridSetup.sh -dryRunForUpgrade` command registers the new Oracle Grid Infrastructure home in the Oracle Inventory (oraInventory).

8. Relaunch the installer from the same Grid home without any flag to start an actual upgrade.

```
$ /u01/app/23.0.0/grid/gridSetup.sh
```

 **Note:**

If you need to apply patches before performing the upgrade, then use the `OPatch` utility to apply in-place patches on each cluster node.

Related Topics

- [Upgrading Oracle Grid Infrastructure Using Setup Wizard](#)
Complete this procedure to upgrade Oracle Grid Infrastructure (Oracle Clusterware and Oracle Automatic Storage Management) from an earlier release using the setup wizard.

Understanding Rolling Upgrades Using Batches

You can perform rolling upgrades of Oracle Grid Infrastructure in batches.

You can use `root` user automation to automate running the `rootupgrade.sh` script during the upgrade. When you use `root` user automation, you can divide the nodes into groups, or batches, and start upgrades of these batches. Between batches, you can move services from nodes running the previous release to the upgraded nodes, so that services are not affected by the upgrade. Oracle recommends that you use `root` automation, and allow the `rootupgrade.sh` script to stop and start instances automatically. You can also continue to run `root` scripts manually.

When you upgrade Oracle Grid Infrastructure without using `root` user automation, you upgrade the entire cluster. You cannot select or de-select individual nodes for upgrade. Oracle does not support attempting to add additional nodes to a cluster during a rolling upgrade. Oracle recommends that you leave Oracle RAC instances running when upgrading Oracle Clusterware. When you start the `root` script on each node, the database instances on that node are shut down and then the `rootupgrade.sh` script starts the instances again.

Restrictions for Selecting Nodes for Batch Upgrades

The following restrictions apply when selecting nodes in batches for upgrade:

- You can pool nodes in batches for upgrade, up to a maximum of three batches.
- The local node, where Oracle Universal Installer (OUI) is running, must be upgraded in batch one.

Performing Rolling Upgrade of Oracle Grid Infrastructure

Review this information to perform rolling upgrade of Oracle Grid Infrastructure.

- [Upgrading Oracle Grid Infrastructure Using Setup Wizard](#)
Complete this procedure to upgrade Oracle Grid Infrastructure (Oracle Clusterware and Oracle Automatic Storage Management) from an earlier release using the setup wizard.
- [Upgrading Oracle Grid Infrastructure Using Command-Line Interface](#)
Complete this procedure to upgrade Oracle Grid Infrastructure (Oracle Clusterware and Oracle Automatic Storage Management) from an earlier release using the command-line interface.
- [Completing an Oracle Clusterware Upgrade when Nodes Become Unreachable](#)
If some nodes become unreachable in the middle of an upgrade, then you cannot complete the upgrade, because the upgrade script (`rootupgrade.sh`) did not run on the unreachable nodes. Because the upgrade is incomplete, Oracle Clusterware remains in the previous release.
- [Joining Inaccessible Nodes After Forcing an Upgrade](#)
Use this procedure to join inaccessible nodes after a force cluster upgrade.
- [Changing the First Node for Install and Upgrade](#)
If the first node becomes inaccessible, you can force another node to be the first node for installation or upgrade.

Upgrading Oracle Grid Infrastructure Using Setup Wizard

Complete this procedure to upgrade Oracle Grid Infrastructure (Oracle Clusterware and Oracle Automatic Storage Management) from an earlier release using the setup wizard.

At any time during the upgrade, if you have a question about what you are being asked to do, or what input you are required to provide during upgrade, click the **Help** button on the installer page.

Note:

- Oracle ASM is upgraded as part of the Oracle Grid Infrastructure upgrade.
- You must remove Grid Infrastructure Management Repository (GIMR) before starting the upgrade.

You should have your network information, storage information, and operating system users and groups available to you before you start upgrade, and you should be prepared to run root scripts.

1. As the `grid` user, download the Oracle Grid Infrastructure image files and extract the files to the Grid home.

For example:

```
mkdir -p /u01/app/23.0.0/grid
chown grid:oinstall /u01/app/23.0.0/grid
cd /u01/app/23.0.0/grid
unzip -q download_location/grid_home.zip
```

download_location/grid_home.zip is the path of the downloaded Oracle Grid Infrastructure image file.

Note:

- You must extract the image software into the directory where you want your Grid home to be located.
- Download and copy the Oracle Grid Infrastructure image files to the local node only. During upgrade, the software is copied and installed on all other nodes in the cluster.

2. Confirm if Grid Infrastructure Management Repository (GIMR) was configured in the earlier release.

```
srvctl config mgmtdb
```

3. Confirm if Oracle Fleet Patching and Provisioning (Oracle FPP) was configured in central server mode in the earlier release.

```
srvctl config rhpserver
```

 **Note:**

- If Oracle FPP is configured on your cluster, then you are recommended to use the Oracle FPP Self-Upgrade feature for smooth migration of the metadata from GIMR to the new metadata repository. Refer to Oracle Fleet Patching and Provisioning Self Upgrade for more information about how to use the Oracle FPP Self-Upgrade feature.
- If you upgrade Oracle Grid Infrastructure using this procedure, then you must re-configure Oracle FPP metadata repository to use the Oracle FPP Server. Refer to Migrating Metadata from GIMR to Oracle FPP Metadata Repository for steps to re-configure Oracle FPP metadata repository.

4. If the GIMR was configured in the earlier release and Oracle FPP was configured in central mode, then export the Oracle FPP Metadata, export the CHA models, and remove GIMR from the existing Oracle Grid Infrastructure installation.

```
Grid_home/crs/install/reposScript.sh -  
export_dir=dir_to_export_CHA_model_and_Oracle_FPP_metadata
```

 **Note:**

- Exporting CHA models is optional. If the export fails, then you can continue removing the GIMR.
- You can remove GIMR independent of the upgrade to Oracle Grid Infrastructure 23ai.

5. Start the Oracle Grid Infrastructure wizard by running the following command.

```
/u01/app/23.0.0/grid/gridSetup.sh
```

6. Select the **Upgrade Oracle Grid Infrastructure:** option to upgrade Oracle Grid Infrastructure (Oracle Clusterware and Oracle ASM).
7. On the Node Selection page, ensure that all cluster nodes are selected.

 **Note:**

If any cluster node is unreachable, then select **Skip upgrade on unreachable nodes**. Otherwise, the upgrade will not complete until the unreachable nodes become reachable.

8. Select installation options as prompted. Oracle recommends that you configure `root` script automation, so that the `rootupgrade.sh` script can be run automatically during the upgrade.
 9. Run the `root` scripts, either automatically or manually:
 - **Running root scripts automatically:**
If you have configured `root` script automation, then use the pause between batches to relocate services from the nodes running the previous release to the new release.
 - **Running root scripts manually**
If you have not configured `root` script automation, then when prompted, run the `rootupgrade.sh` script on each node in the cluster that you want to upgrade.
- If you run the `root` scripts manually, then run the script on the local node first. The script shuts down the earlier release installation, replaces it with the new Oracle Clusterware release, and starts the new Oracle Clusterware installation. After the script completes successfully, you can run the script in parallel on all nodes except for one, which you select as the last node. When the script is run successfully on all the nodes except the last node, run the script on the last node.
10. Because the Oracle Grid Infrastructure home is in a different location than the former Oracle Clusterware and Oracle ASM homes, update any scripts or applications that use utilities, libraries, or other files that reside in the Oracle Clusterware and Oracle ASM homes.
 11. Update the Oracle Enterprise Manager target parameters as described in the topic *Updating Oracle Enterprise Manager Cloud Control Target Parameters*.

 **Note:**

- After upgrading to Oracle Grid Infrastructure 23ai, remove the `ADR_BASE=/u01/app/grid` entry from `$ORACLE_HOME/network/admin/sqlnet.ora` file, if you use Oracle ASM for database storage.
- At the end of the upgrade, if you set the Oracle Cluster Registry (OCR) backup location manually to the earlier release Oracle Clusterware home (CRS home), then you must change the OCR backup location to the new Oracle Grid Infrastructure home (Grid home). If you did not set the OCR backup location manually, then the backup location is changed for you during the upgrade.
- Because upgrades of Oracle Clusterware are out-of-place upgrades, the previous release Oracle Clusterware home cannot be the location of the current release OCR backups. Backups in the old Oracle Clusterware home can be deleted.
- If the cluster being upgraded has a single disk group that stores the OCR, OCR backup, Oracle ASM password, and the Oracle ASM password file backup, then Oracle recommends that you create a separate disk group or use another existing disk group and store the OCR backup and Oracle ASM password file backup in that disk group.

Related Topics

- *Oracle Clusterware Administration and Deployment Guide*

Upgrading Oracle Grid Infrastructure Using Command-Line Interface

Complete this procedure to upgrade Oracle Grid Infrastructure (Oracle Clusterware and Oracle Automatic Storage Management) from an earlier release using the command-line interface.

Note:

- Oracle ASM is upgraded as part of the Oracle Grid Infrastructure upgrade.
- You must remove Grid Infrastructure Management Repository (GIMR) before starting the upgrade.

You should have your network information, storage information, and operating system users and groups available to you before you start upgrade, and you should be prepared to run root scripts.

1. As the `grid` user, download the Oracle Grid Infrastructure image files and extract the files to the Grid home.

For example:

```
mkdir -p /u01/app/23.0.0/grid
chown grid:oinstall /u01/app/23.0.0/grid
cd /u01/app/23.0.0/grid
unzip -q download_location/grid_home.zip
```

download_location/grid_home.zip is the path of the downloaded Oracle Grid Infrastructure image file.

Note:

- You must extract the image software into the directory where you want your Grid home to be located.
- Download and copy the Oracle Grid Infrastructure image files to the local node only. During upgrade, the software is copied and installed on all other nodes in the cluster.

2. Confirm if Grid Infrastructure Management Repository (GIMR) was configured in the earlier release.

```
srvctl config mgmtadb
```

3. Confirm if Oracle Fleet Patching and Provisioning (Oracle FPP) was configured in central server mode in the earlier release.

```
srvctl config rhpserver
```

 **Note:**

- If Oracle FPP is configured on your cluster, then you are recommended to use the Oracle FPP Self-Upgrade feature for smooth migration of the metadata from GIMR to the new metadata repository. Refer to Oracle Fleet Patching and Provisioning Self Upgrade for more information about how to use the Oracle FPP Self-Upgrade feature.
- If you upgrade Oracle Grid Infrastructure using this procedure, then you must re-configure Oracle FPP metadata repository to use the Oracle FPP Server. Refer to Migrating Metadata from GIMR to Oracle FPP Metadata Repository for steps to re-configure Oracle FPP metadata repository.

4. If the GIMR was configured in the earlier release and Oracle FPP was configured in central mode, then export the Oracle FPP Metadata to re-configure Oracle FPP after the upgrade and remove GIMR from the existing Oracle Grid Infrastructure installation.

```
Grid_home/crs/install/reposScript.sh -
export_dir=dir_to_export_CHA_model_and_Oracle_FPP_metadata
```

 **Note:**

- Exporting CHA models is optional. If the export fails, then you can continue removing the GIMR.
- You can remove GIMR even if you do not upgrade to Oracle Grid Infrastructure 23ai. However, it is mandatory to remove GIMR before the upgrade.

5. Start the Oracle Grid Infrastructure installation by running the following command.

```
cd /u01/app/23.0.0/grid
./gridSetup.sh -upgrade -ORACLE_BASE /u01/app/grid [-ignoreDownNodes] -
executeConfigTools -executeRootScript -configMethod ROOT
```

6. Provide the `root` user password when prompted.
7. Because the Oracle Grid Infrastructure home is in a different location than the former Oracle Clusterware and Oracle ASM homes, update any scripts or applications that use utilities, libraries, or other files that reside in the Oracle Clusterware and Oracle ASM homes.
8. Update the Oracle Enterprise Manager target parameters as described in the topic *Updating Oracle Enterprise Manager Cloud Control Target Parameters*.

 **Note:**

- After upgrading to Oracle Grid Infrastructure 23ai, remove the `ADR_BASE=/u01/app/grid` entry from `$ORACLE_HOME/network/admin/sqlnet.ora` file, if you use Oracle ASM for database storage.
- At the end of the upgrade, if you set the Oracle Cluster Registry (OCR) backup location manually to the earlier release Oracle Clusterware home (CRS home), then you must change the OCR backup location to the new Oracle Grid Infrastructure home (Grid home). If you did not set the OCR backup location manually, then the backup location is changed for you during the upgrade.
- Because upgrades of Oracle Clusterware are out-of-place upgrades, the previous release Oracle Clusterware home cannot be the location of the current release OCR backups. Backups in the old Oracle Clusterware home can be deleted.
- If the cluster being upgraded has a single disk group that stores the OCR, OCR backup, Oracle ASM password, and the Oracle ASM password file backup, then Oracle recommends that you create a separate disk group or use another existing disk group and store the OCR backup and Oracle ASM password file backup in that disk group.

Related Topics

- *Oracle Clusterware Administration and Deployment Guide*

Completing an Oracle Clusterware Upgrade when Nodes Become Unreachable

If some nodes become unreachable in the middle of an upgrade, then you cannot complete the upgrade, because the upgrade script (`rootupgrade.sh`) did not run on the unreachable nodes. Because the upgrade is incomplete, Oracle Clusterware remains in the previous release.

1. Confirm that the upgrade is incomplete by entering the following command:

```
$ crsctl query crs activeversion
```

The active release should be the source release.

2. To resolve this problem, run the `rootupgrade.sh` command with the `-force` flag using the following syntax:

```
Grid_home/rootupgrade -force
```

For example:

```
# /u01/app/23.0.0/grid/rootupgrade -force
```

This command forces the upgrade to complete. The force cluster upgrade has the following limitations:

- All active nodes must be upgraded to the newer release.

- All inactive nodes (accessible or inaccessible) may be either upgraded or not upgraded.
 - For inaccessible nodes, after patch set upgrades, you can delete the node from the cluster. If the node becomes accessible later, and the patch version upgrade path is supported, then you can upgrade it to the new patch version.
3. Verify that the upgrade has completed by using the following command:

```
$ crsctl query crs activeversion -f
Oracle Clusterware active version on the cluster is [23.0.0.0.0].
The cluster upgrade state is [FORCED]. The cluster active patch level is
[0].
```

The active release should be the upgraded release. The upgrade state `FORCED` indicates that Oracle Clusterware upgrade was completed forcibly on all reachable nodes, while one or more cluster nodes were unreachable. You can either upgrade or delete the unreachable cluster nodes to change the cluster upgrade state from `FORCED` to `NORMAL`.

Related Topics

- Oracle Clusterware Upgrade Status

Joining Inaccessible Nodes After Forcing an Upgrade

Use this procedure to join inaccessible nodes after a force cluster upgrade.

Starting with Oracle Grid Infrastructure 12c, after you complete a force cluster upgrade, you can use the procedure described here to join inaccessible nodes to the cluster as an alternative to deleting the nodes, which was required in earlier releases. To use this option, you must already have Oracle Grid Infrastructure 23ai software installed on the nodes.

1. Log in as the `root` user on the node that you want to join to the cluster.
2. Change directory to the Oracle Grid Infrastructure home directory:

```
$ cd Grid_home
```

3. Run the following command, where `upgraded_node` is one of the cluster nodes that is upgraded successfully:

```
$ rootupgrade.sh -join -existingnode upgraded_node
```

Changing the First Node for Install and Upgrade

If the first node becomes inaccessible, you can force another node to be the first node for installation or upgrade.

During installation, if `root.sh` fails to complete on the first node, run the following command on another node using the `-force` option:

```
root.sh -force -first
```

For upgrade:

```
rootupgrade.sh -force -first
```

About Upgrading Oracle Grid Infrastructure Using Oracle Fleet Patching and Provisioning

Oracle Fleet Patching and Provisioning (Oracle FPP) is a software lifecycle management method for provisioning and patching Oracle homes.

Oracle Fleet Patching and Provisioning enables you to install clusters, and provision, patch, and upgrade Oracle Grid Infrastructure, Oracle Database, and Oracle Restart homes. The supported versions are 12.2, 18c, 19c, 21c, and 23ai. You can also provision applications and middleware using Oracle FPP. A single cluster, known as the Oracle Fleet Patching and Provisioning Server, stores and manages standardized images, called gold images, which can be provisioned to any number of nodes. After deployment, you can expand and contract clusters and Oracle RAC Databases.

You can provision Oracle Grid Infrastructure on a remote set of nodes in a cloud computing environment from a single cluster where you store templates of Oracle homes as images (called gold images) of Oracle software, such as databases, middleware, and applications.

Oracle Fleet Patching and Provisioning

Deploying Oracle software using Oracle FPP has the following advantages:

- Ensures standardization and enables high degrees of automation with gold images and managed lineage of deployed software.
- Supports change management. With standardized Oracle homes, an administrator has better control of the hosted Oracle software and can easily manage the mass deployment and maintenance of the software through a single location for change management.
- Minimizes downtime during patching and upgrades, eases rollbacks, and makes provisioning for large systems easier and more efficient.
- Reduces the cumulative time to patch software images, since a single Oracle home may be used for many database instances.

See Also:

Oracle Clusterware Administration and Deployment Guide for information about setting up the Oracle Fleet Patching and Provisioning Server and Client, creating and using gold images for provisioning and patching Oracle Grid Infrastructure, Oracle Database, and Oracle Restart homes.

Updating Oracle Enterprise Manager Cloud Control Target Parameters

After upgrading Oracle Grid Infrastructure, upgrade the Enterprise Manager Cloud Control target.

Because Oracle Grid Infrastructure 23ai is an out-of-place upgrade of the Oracle Clusterware home in a new location (the Oracle Grid Infrastructure for a cluster home, or Grid home), the path for the `CRS_HOME` parameter in some parameter files must be changed. If you do not

change the parameter, then you encounter errors such as "cluster target broken" on Oracle Enterprise Manager Cloud Control.

To resolve the issue, update the Enterprise Manager Cloud Control target, and then update the Enterprise Manager Agent Base Directory on each cluster member node running an agent.

- [Updating the Enterprise Manager Cloud Control Target After Upgrades](#)
After upgrading Oracle Grid Infrastructure, update the Enterprise Manager Target with the new Grid home path.
- [Updating the Enterprise Manager Agent Base Script After Upgrades](#)
After upgrading Oracle Grid Infrastructure, update the Enterprise Manager Agent Base Script on each cluster member node running an agent.
- [Registering Resources with Oracle Enterprise Manager After Upgrades](#)
After upgrading Oracle Grid Infrastructure, add the new resource targets to Oracle Enterprise Manager Cloud Control.

Updating the Enterprise Manager Cloud Control Target After Upgrades

After upgrading Oracle Grid Infrastructure, update the Enterprise Manager Target with the new Grid home path.

1. Log in to Enterprise Manager Cloud Control.
2. Navigate to the **Targets** menu, and then to the **Cluster** page.
3. Click a cluster target that was upgraded.
4. Click **Cluster**, then **Target Setup**, and then **Monitoring Configuration** from the menu.
5. Update the value for **Oracle Home** with the new Grid home path.
6. Save the updates.

Updating the Enterprise Manager Agent Base Script After Upgrades

After upgrading Oracle Grid Infrastructure, update the Enterprise Manager Agent Base Script on each cluster member node running an agent.

The Agent Base directory is a directory where the Management Agent home is created. The Management Agent home is in the path *Agent_Base_Directory/core/EMAgent_Version*. For example, if the Agent Base directory is `/u01/app/emagent`, then the Management Agent home is created as `/u01/app/emagent/core/13.1.1.0`.

1. Navigate to the `bin` directory in the Management Agent home.
2. In the `/u01/app/emagent/core/13.1.1.0/bin` directory, open the file `emctl` with a text editor.
3. Locate the parameter `CRS_HOME`, and update the parameter to the new Grid home path.
4. Repeat steps 1 to 3 on each node of the cluster with an Enterprise Manager agent.

Registering Resources with Oracle Enterprise Manager After Upgrades

After upgrading Oracle Grid Infrastructure, add the new resource targets to Oracle Enterprise Manager Cloud Control.

Discover and add new resource targets in Oracle Enterprise Manager after Oracle Grid Infrastructure upgrade. The following procedure provides an example of discovering an Oracle ASM listener target after upgrading Oracle Grid Infrastructure:

1. Log in to Oracle Enterprise Manager Cloud Control.
2. From the **Setup** menu, select **Add Target**, and then select **Add Targets Manually**.
The Add Targets Manually page is displayed.
3. In the Add Targets page, select the **Add Using Guided Process** option and **Target Type** as Oracle Database, Listener and Automatic Storage Management.
For any other resource to be added, select the appropriate **Target Type** in Oracle Enterprise Manager discovery wizard.
4. Click **Add Using Guided Process**.
The Target Discover wizard is displayed.
5. For the **Specify Host or Cluster** field, click on the **Search** icon and search for **Target Types** of `Hosts`, and select the corresponding Host.
6. Click **Next**.
7. In the Target Discovery: Results page, select the discovered Oracle ASM Listener target, and click **Configure**.
8. In the Configure Listener dialog box, specify the listener properties and click **OK**.
9. Click **Next** and complete the discovery process.
The listener target is discovered in Oracle Enterprise Manager with the status as Down.
10. From the **Targets** menu, select the type of target.
11. Click the target name to navigate to the target home page.
12. From the host, database, middleware target, or application menu displayed on the target home page, select **Target Setup**, then select **Monitoring Configuration**.
13. In the Monitoring Configuration page for the listener, specify the host name in the **Machine Name** field and the password for the `ASMSNMP` user in the **Password** field.
14. Click **OK**.

Oracle ASM listener target is displayed with the correct status.

Similarly, you can add other clusterware resources to Oracle Enterprise Manager after an Oracle Grid Infrastructure upgrade.

Unlocking and Deinstalling the Previous Release Grid Home

After upgrading from previous releases, if you want to deinstall the previous release Oracle Grid Infrastructure home, then you must first change the permission and ownership of the previous release Grid home.

1. As the `root` user, change the permission and ownership of the previous release Grid home using the following command syntax, where `oldGH` is the previous release Grid home,

giowner is the Oracle Grid Infrastructure installation owner, and *oldGHParent* is the parent directory of the previous release Grid home:

```
#chmod -R 755 oldGH
#chown -R giowner oldGH
#chown giowner oldGHParent
```

For example:

```
#chmod -R 755 /u01/app/21.0.0/grid
#chown -R grid /u01/app/21.0.0/grid
#chown grid /u01/app/21.0.0/
```

2. As the `grid` user, and use the `-checkonly` parameter from previous release Grid home `oldGH/deinstall` directory to check the status of the Oracle software home configuration.

```
oldGH/deinstall/deinstall -checkonly -silent -o /tmp/ -tmpdir /tmp
```

3. Use the `deinstall` command from previous release Grid home `oldGH/deinstall` directory to deinstall the previous release Grid home.

```
oldGH/deinstall/deinstall -silent -tmpdir /tmp/rsp_file
```

4. As the `root` user, run the `rootdeinstall.sh` script from the `/tmp/deinstall<date>/` directory.

```
/tmp/deinstall<date>/rootdeinstall.sh
```

Caution:

You must use the `deinstall` command from the same release to remove Oracle software. Do not run the `deinstall` command from a later release to remove Oracle software from an earlier release. For example, do not run the `deinstall` command from the 23.0.0.0.0 Oracle home to remove Oracle software from an existing 21.0.0.0.0 Oracle home.

Checking Cluster Health Monitor Repository Size After Upgrading

If you are upgrading Oracle Grid Infrastructure from a prior release using IPD/OS to the current release, then review the Cluster Health Monitor repository size (the CHM repository).

1. Review your CHM repository needs, and determine if you need to increase the repository size to maintain a larger CHM repository.

 **Note:**

Your previous IPD/OS repository is deleted when you install Oracle Grid Infrastructure.

By default, the CHM repository size is a minimum of either 1GB or 3600 seconds (1 hour), regardless of the size of the cluster.

2. To enlarge the CHM repository, use the following command syntax, where *RETENTION_TIME* is the size of CHM repository in number of seconds:

```
oclumon manage -repos changeretentiontime RETENTION_TIME
```

For example, to set the repository size to four hours:

```
oclumon manage -repos changeretentiontime 14400
```

The value for *RETENTION_TIME* must be more than 3600 (one hour) and less than 259200 (three days). If you enlarge the CHM repository size, then you must ensure that there is local space available for the repository size you select on each node of the cluster. If you do not have sufficient space available, then you can move the repository to shared storage.

Downgrading Oracle Clusterware to an Earlier Release

After a successful or a failed upgrade, you can downgrade Oracle Clusterware to the previous release.

- [About Oracle Grid Infrastructure Downgrades](#)
Understand the process and impacts of Oracle Grid Infrastructure downgrades.
- [Options for Oracle Grid Infrastructure Downgrades](#)
You can downgrade Oracle Grid Infrastructure to earlier releases after a successful or a failed upgrade.
- [Restrictions for Oracle Grid Infrastructure Downgrades](#)
Review the following information for restrictions and changes for downgrading Oracle Grid Infrastructure installations.
- [Downgrading Oracle Grid Infrastructure](#)
Use this procedure to downgrade Oracle Grid Infrastructure after a successful upgrade.
- [Downgrading Oracle Grid Infrastructure when Upgrade Fails](#)
If upgrade of Oracle Grid Infrastructure fails before CVU post upgrade checks succeed, then you can run `gridSetup.sh` and downgrade Oracle Grid Infrastructure to the earlier release.
- [Downgrading Oracle Grid Infrastructure Using Online Terminate Upgrade](#)
If upgrade of Oracle Grid Infrastructure fails before setting the active version of Oracle Clusterware, then follow these steps to downgrade Oracle Grid Infrastructure to the earlier release.

About Oracle Grid Infrastructure Downgrades

Understand the process and impacts of Oracle Grid Infrastructure downgrades.

Downgrading Oracle Clusterware restores the Oracle Clusterware configuration to the state it was in before the Oracle Grid Infrastructure upgrade. Any configuration changes you performed during or after the Oracle Grid Infrastructure upgrade are removed and cannot be recovered.

To restore Oracle Clusterware to the previous release, use the downgrade procedure for the release to which you want to downgrade.

 **Note:**

- You can downgrade the cluster nodes in any sequence. You can downgrade all cluster nodes except one, in parallel. You must downgrade the last node after you downgrade all other nodes.
- When downgrading after a failed upgrade, if the `rootcrs.sh` or `rootcrs.bat` file does not exist on a node, then instead of executing the script, use the command `perl rootcrs.pl`. Use the Perl interpreter located in the Oracle Home directory.

Options for Oracle Grid Infrastructure Downgrades

You can downgrade Oracle Grid Infrastructure to earlier releases after a successful or a failed upgrade.

Downgrade options include the following earlier releases:

- Oracle Grid Infrastructure downgrade to Oracle Grid Infrastructure 21c.
- Oracle Grid Infrastructure downgrade to Oracle Grid Infrastructure 19c.

 **Note:**

When you downgrade Oracle Grid Infrastructure to an earlier release, for example from Oracle Grid Infrastructure 23ai to Oracle Grid Infrastructure 21c, the later release RAC databases already registered with Oracle Grid Infrastructure will not start after the downgrade.

Restrictions for Oracle Grid Infrastructure Downgrades

Review the following information for restrictions and changes for downgrading Oracle Grid Infrastructure installations.

- You can only downgrade to the Oracle Grid Infrastructure release you upgraded from. For example, if you upgraded from Oracle Grid Infrastructure 19c to Oracle Grid Infrastructure 23ai, you can only downgrade to Oracle Grid Infrastructure 19c.

Downgrading Oracle Grid Infrastructure

Use this procedure to downgrade Oracle Grid Infrastructure after a successful upgrade.

1. As the `root` user, use the command syntax `rootcrs.sh -downgrade` from 23ai Grid home to downgrade Oracle Grid Infrastructure on all nodes, in any sequence. For example:

```
# $ORACLE_HOME/crs/install/rootcrs.sh -downgrade
```

Run this command from a directory that has write permissions for the Oracle Grid Infrastructure installation user. You can run the downgrade script in parallel on all cluster nodes, but one.

2. Downgrade the last node after you downgrade all other nodes:

```
# $ORACLE_HOME/crs/install/rootcrs.sh -downgrade
```

3. Set previous release Grid home as the active Oracle Clusterware home:

- a. On any of the cluster member nodes where the `rootupgrade` script has run successfully, log in as the Oracle Grid Infrastructure installation owner.
- b. Use the following command to start the installer, where the path you provide for `ORACLE_HOME` is the location of the home directory from the earlier Oracle Clusterware installation.

```
$ cd $ORACLE_HOME/oui/bin
$ ./runInstaller -nowait -waitforcompletion -ignoreSysPrereqs
-updateNodeList -silent CRS=true
ORACLE_HOME=pre-upgrade-grid-home
"CLUSTER_NODES=node1,node2,node3"
```

pre-upgrade-grid-home is the previous release Grid home.

4. As the `root` user, start the Oracle Clusterware stack on all nodes from previous release Grid home.

```
# crsctl start crs
```

Downgrading Oracle Grid Infrastructure when Upgrade Fails

If upgrade of Oracle Grid Infrastructure fails before CVU post upgrade checks succeed, then you can run `gridSetup.sh` and downgrade Oracle Grid Infrastructure to the earlier release.

Run this procedure to downgrade Oracle Clusterware only when the upgrade fails before CVU post upgrade checks succeed.

- From the later release Grid home, run `gridSetup.sh` in silent mode, to downgrade Oracle Clusterware:

```
$ /u01/app/23.0.0/grid/gridSetup.sh -silent -downgrade [-nodes]
nodes_to_be_downgraded
[-oldHome] pre-upgrade-grid-home
[-configmethod] root | sudo [-sudopath path_to_sudo_program]
[-sudoerusername sudoer_name]
```

**Note:**

You can downgrade the cluster nodes in any sequence.

Downgrading Oracle Grid Infrastructure Using Online Terminate Upgrade

If upgrade of Oracle Grid Infrastructure fails before setting the active version of Oracle Clusterware, then follow these steps to downgrade Oracle Grid Infrastructure to the earlier release.

Run this procedure to downgrade Oracle Clusterware only when the upgrade fails before root script runs the `crsctl set crs activeversion` command on the last node. Use this procedure for downgrading Oracle Grid Infrastructure if there is a need to avoid downtime of the whole cluster. This procedure downgrades the cluster to the previous release. Because Oracle ASM and database operations are limited in this state, it is required to downgrade the cluster as soon as possible. Complete the downgrade of Oracle Grid Infrastructure as per the procedure documented in *Downgrading Oracle Grid Infrastructure after Upgrade Fails*.

1. Shut down the Oracle Grid Infrastructure stack on the node that you are downgrading.

```
crsctl stop crs
```

2. Run the following command on all cluster nodes on which Oracle Grid Infrastructure is running, but not on the node that you are downgrading.

```
clscfg -nodedowngrade -h hostname
```

hostname is the name of the node that you are downgrading.

3. From the later release Grid home, run the following command on all cluster nodes, which are successfully upgraded, to downgrade Oracle Clusterware.

```
rootcrs.sh -downgrade -online
```

If `rootcrs.sh` is not present, then use `rootcrs.pl`.

4. Start Oracle Grid Infrastructure stack on all the nodes from the earlier release Grid home.

```
crsctl start crs
```

**Note:**

You can downgrade the successfully upgraded cluster nodes in any sequence.

5. On the last node where the Grid Infrastructure stack from the earlier release is running, unset the Oracle ASM rolling migration mode as follows:
 - Log in as `grid` user, and run the following command as SYSASM user on the Oracle ASM instance:

```
SQL> ALTER SYSTEM STOP ROLLING MIGRATION;
```

Completing Failed or Interrupted Installations and Upgrades

If Oracle Universal Installer (OUI) exits on the node from which you started the upgrade, or the node reboots before you confirm that the `rootupgrade.sh` script was run on all nodes, then the upgrade remains incomplete.

In an incomplete installation or upgrade, configuration assistants still need to run, and the new Grid home still needs to be marked as active in the central Oracle inventory. You must complete the installation or upgrade on the affected nodes manually.

- [Completing Failed Installations and Upgrades](#)
Understand how to join nodes to the cluster after installation or upgrade fails on some nodes.
- [Continuing Incomplete Upgrade of First Node](#)
Review this information to complete the upgrade, if upgrade of Oracle Grid Infrastructure fails on the first node.
- [Continuing Incomplete Upgrades on Remote Nodes](#)
Review this information to continue incomplete upgrade on remote nodes.
- [Continuing Incomplete Installation on First Node](#)
Review this information to continue an incomplete installation of Oracle Grid Infrastructure, if installation fails on the first node.
- [Continuing Incomplete Installation on Remote Nodes](#)
Review this information to continue incomplete installation on remote nodes.

Completing Failed Installations and Upgrades

Understand how to join nodes to the cluster after installation or upgrade fails on some nodes.

If installation or upgrade of Oracle Grid Infrastructure on some nodes fails, and the installation or upgrade completes with only successful nodes in the cluster, then follow this procedure to add the failed nodes to the cluster.

1. Remove the Oracle Grid Infrastructure software from the failed nodes:

```
Grid_home/deinstall/deinstall -local
```

2. As the `root` user, from a node where Oracle Clusterware is installed, delete the failed nodes using the `delete node` command:

```
Grid_home/bin/crsctl delete node -n node_name
```

node_name is the node to be deleted.

3. Run the Oracle Grid Infrastructure installation wizard and follow the steps in the wizard to add the nodes:

```
Grid_home/gridSetup.sh
```

The nodes are added to the cluster.

Continuing Incomplete Upgrade of First Node

Review this information to complete the upgrade, if upgrade of Oracle Grid Infrastructure fails on the first node.

1. If the root script failure indicated a need to reboot, through the message `CLSRSC-400`, then reboot the first node (the node where the upgrade was started). Otherwise, manually fix or clear the error condition, as reported in the error output.
2. If necessary, log in as `root` to the first node. Change directory to the new Grid home on the first node, and run the `rootupgrade.sh` script on that node again. For example:

```
[root@node1]# cd Grid_home
[root@node1]# ./rootupgrade.sh
```

3. Complete the upgrade of all other nodes in the cluster.
Complete the upgrade of all other nodes in the cluster.

```
[root@node2]# ./rootupgrade.sh
```

4. Configure a response file, and provide passwords for the installation.
5. To complete the upgrade, log in as the Grid installation owner, and run `gridSetup.sh`, located in the `Grid_home`, specifying the response file that you created. For example, where the response file is `gridinstall.rsp`:

```
[grid@node1]$ Grid_home/gridSetup.sh -executeConfigTools -responseFile
Grid_home/install/response/gridinstall.rsp
```

Note:

When you reupgrade Oracle Grid Infrastructure, you must use the `-all` flag with the `executeConfigTools` command to run all the configuration tools.

Continuing Incomplete Upgrades on Remote Nodes

Review this information to continue incomplete upgrade on remote nodes.

1. If the root script failure indicated a need to reboot, through the message `CLSRSC-400`, then reboot the first node (the node where the upgrade was started). Otherwise, manually fix or clear the error condition, as reported in the error output.
2. If root automation is being used, click **Retry** on the OUI instance on the first node.
3. If root automation is not being used, log into the affected node as `root`. Change directory to the Grid home, and run the `rootupgrade.sh` script on that node. For example:

```
[root@node6]# cd Grid_home
[root@node6]# ./rootupgrade.sh
```

Continuing Incomplete Installation on First Node

Review this information to continue an incomplete installation of Oracle Grid Infrastructure, if installation fails on the first node.

1. If the root script failure indicated a need to reboot, through the message `CLSRSC-400`, then reboot the first node (the node where the installation was started). Otherwise, manually fix or clear the error condition, as reported in the error output.
2. If necessary, log in as `root` to the first node. Run the `orainstRoot.sh` script on that node again. For example:

```
$ sudo -s
[root@node1]# cd /u01/app/oraInventory
[root@node1]# ./orainstRoot.sh
```

3. Change directory to the Grid home on the first node, and run the `root` script on that node again. For example:

```
[root@node1]# cd Grid_home
[root@node1]# ./root.sh
```

4. Complete the installation on all other nodes.
5. Configure a response file, and provide passwords for the installation.
6. To complete the installation, log in as the Grid installation owner, and run `gridSetup.sh`, located in the Oracle Grid Infrastructure home, specifying the response file that you created. For example, where the response file is `gridinstall.rsp`:

```
[grid@node1]$ Grid_home/gridSetup.sh -executeConfigTools -
responseFile /u01/app/23.0.0/grid/install/response/gridinstall.rsp
```

Continuing Incomplete Installation on Remote Nodes

Review this information to continue incomplete installation on remote nodes.

1. If the root script failure indicated a need to reboot, through the message `CLSRSC-400`, then reboot the affected node. Otherwise, manually fix or clear the error condition, as reported in the error output.
2. If root automation is being used, click **Retry** on the OUI instance on the first node.
3. If root automation is not being used, follow these steps:
 - a. Log into the affected node as `root`, and run the `orainstRoot.sh` script on that node. For example:

```
$ sudo -s
[root@node6]# cd /u01/app/oraInventory
[root@node6]# ./orainstRoot.sh
```


- b.** Change directory to the Grid home, and run the `root.sh` script on the affected node.
For example:

```
[root@node6]# cd Grid_home
[root@node6]# ./root.sh
```

- 4.** Continue the installation from the OUI instance on the first node.

12

Oracle Grid Infrastructure Postinstallation Tasks

Complete configuration tasks after you install Oracle Grid Infrastructure.

You are required to complete some configuration tasks after Oracle Grid Infrastructure is installed. In addition, Oracle recommends that you complete additional tasks immediately after installation. You must also complete product-specific configuration tasks before you use those products.



Note:

This chapter describes basic configuration only. Refer to product-specific administration and tuning guides for more detailed configuration and tuning information.

- [Required Postinstallation Tasks](#)
Download and apply required patches for your software release after completing your initial installation.
- [Recommended Postinstallation Tasks](#)
Oracle recommends that you complete these tasks after installation.
- [About Changes in Default SGA Permissions for Oracle Database](#)
By default, permissions to read and write to the System Global Area (SGA) are limited to the Oracle software installation owner.
- [Using Earlier Oracle Database Releases with Oracle Grid Infrastructure](#)
Review these topics for information about using earlier Oracle Database releases with Oracle Grid Infrastructure 23ai installations.
- [Relinking Oracle Grid Infrastructure for a Cluster Binaries](#)
After installing Oracle Grid Infrastructure for a cluster, if you modify the Oracle Grid Infrastructure binaries, then you must relink the binaries on Oracle Linux 8 or earlier releases.

Required Postinstallation Tasks

Download and apply required patches for your software release after completing your initial installation.

- [Downloading Release Update Patches](#)
Download and install Release Updates (RU) and Monthly Recommended Patches (MRPs) patches for your Oracle software after you complete your installation.

Downloading Release Update Patches

Download and install Release Updates (RU) and Monthly Recommended Patches (MRPs) patches for your Oracle software after you complete your installation.

Oracle provides quarterly updates in the form of Release Updates (RU) and Monthly Recommended Patches (MRPs). Oracle no longer releases patch sets. For more information, see [My Oracle Support Note 2285040.1](#).

Check the My Oracle Support website for required updates for your installation.

1. Log in to the My Oracle Support website:

<https://support.oracle.com>

 **Note:**

If you are not a My Oracle Support registered user, then click **Register for My Oracle Support** and register.

2. In the **sign in to other Oracle Support portals** section, click **Support for Oracle Hardware, Software, and Managed Cloud services** to log in to My Oracle Support.
3. On the main My Oracle Support page, click **Patches & Updates**.
4. In the **Patch Search** region, select **Product or Family (Advanced)**.
5. On the **Product or Family (Advanced)** display, provide information about the product, release, and platform for which you want to obtain patches, and click **Search**.

The Patch Search pane opens, displaying the results of your search.

6. Select the patch number and click **ReadMe**.

The README page is displayed. It contains information about the patch and how to apply the patches to your installation.

7. Uncompress the Oracle patch updates that you downloaded from My Oracle Support.

 **Note:**

The use of OPatch and OPatchAuto for out-of-place patching continues to be deprecated.

For patching in Oracle Database 23ai, Oracle recommends that you use out-of-place patching using Gold images to apply quarterly release updates (RUs). This deprecation does not affect in-place patching. If you want to perform in-place patching, then OPatch and OPatchAuto continue to be available for this purpose. The Oracle Database 23ai Free release is not supported for patching with RUs.

Related Topics

- [My Oracle Support note 888.1](#)
- [Patch Delivery Methods for Oracle Database](#)

Recommended Postinstallation Tasks

Oracle recommends that you complete these tasks after installation.

- [About Installing Oracle Autonomous Health Framework](#)
Oracle Autonomous Health Framework is pre-installed with Oracle Database.
- [Creating a Fast Recovery Area](#)
During an Oracle Restart installation, you can create only one disk group. During an Oracle Clusterware installation, you can create multiple disk groups. If you plan to add an Oracle Database for a standalone server or an Oracle RAC database, then you should create the fast recovery area for database files.
- [Checking the SCAN Configuration](#)
The Single Client Access Name (SCAN) is a name that is used to provide service access for clients to the cluster.
- [Setting Resource Limits for Oracle Clusterware and Associated Databases and Applications](#)
After you have completed Oracle Grid Infrastructure installation, you can set resource limits in the `Grid_home/crs/install/s_crsconfig_nodename_env.txt` file.

About Installing Oracle Autonomous Health Framework

Oracle Autonomous Health Framework is pre-installed with Oracle Database.

Oracle Autonomous Health Framework performs proactive health checks and collects diagnostics data for the Oracle software stack. Oracle Autonomous Health Framework updates are available on My Oracle Support and also shipped with Oracle Database Release Updates.

Oracle recommends that you update to the latest version of Oracle Autonomous Health Framework by either applying the latest Database Release Updates or by downloading and installing it from My Oracle Support Note 2550798.1:

<https://support.oracle.com/epmos/faces/DocContentDisplay?id=2550798.1&parent=DOCUMENTATION&sourceId=USERGUIDE>

Oracle Autonomous Health Framework includes the functionality from Oracle ORAchk, Oracle EXAchk, and Oracle Trace File Analyzer (TFA). Oracle Autonomous Health Framework extends health check coverage to the entire Oracle software stack, based on critical and reoccurring problems. Oracle Autonomous Health Framework proactively scans for known problems with Oracle products and deployments, including the following:

- Single-instance Oracle Database
- Oracle Grid Infrastructure
- Oracle Real Application Clusters
- Maximum Availability Architecture (MAA) Validation
- Upgrade Readiness Validations
- Oracle GoldenGate
- Oracle Exadata
- Oracle SuperCluster
- Oracle Zero Data Loss Recovery Appliance

Related Topics

- [Oracle Autonomous Health Framework Checks and Diagnostics User's Guide](#)

Creating a Fast Recovery Area

During an Oracle Restart installation, you can create only one disk group. During an Oracle Clusterware installation, you can create multiple disk groups. If you plan to add an Oracle Database for a standalone server or an Oracle RAC database, then you should create the fast recovery area for database files.

- [About the Fast Recovery Area and the Fast Recovery Area Disk Group](#)
The fast recovery area is a unified storage location for all Oracle Database files related to recovery. Enabling rapid backups for recent data can reduce requests to system administrators to retrieve backup tapes for recovery operations.
- [Creating the Fast Recovery Area Disk Group](#)
Procedure to create the fast recovery area disk group.

About the Fast Recovery Area and the Fast Recovery Area Disk Group

The fast recovery area is a unified storage location for all Oracle Database files related to recovery. Enabling rapid backups for recent data can reduce requests to system administrators to retrieve backup tapes for recovery operations.

Database administrators can define the `DB_RECOVERY_FILE_DEST` parameter to the path for the fast recovery area to enable on disk backups and rapid recovery of data. When you enable fast recovery in the `init.ora` file, Oracle Database writes all RMAN backups, archive logs, control file automatic backups, and database copies to the fast recovery area. RMAN automatically manages files in the fast recovery area by deleting obsolete backups and archiving files no longer required for recovery.

Oracle recommends that you create a fast recovery area disk group. Oracle Clusterware files and Oracle Database files can be placed on the same disk group, and you can also place fast recovery files in the same disk group. However, Oracle recommends that you create a separate fast recovery disk group to reduce storage device contention.

The fast recovery area is enabled by setting the `DB_RECOVERY_FILE_DEST` parameter. The size of the fast recovery area is set with `DB_RECOVERY_FILE_DEST_SIZE`. As a general rule, the larger the fast recovery area, the more useful it becomes. For ease of use, Oracle recommends that you create a fast recovery area disk group on storage devices that can contain at least three days of recovery information. Ideally, the fast recovery area is large enough to hold a copy of all of your data files and control files, the online redo logs, and the archived redo log files needed to recover your database using the data file backups kept under your retention policy.

Multiple databases can use the same fast recovery area. For example, assume you have created a fast recovery area disk group on disks with 150 GB of storage, shared by 3 different databases. You can set the size of the fast recovery for each database depending on the importance of each database. For example, if `database1` is your least important database, `database2` is of greater importance, and `database3` is of greatest importance, then you can set different `DB_RECOVERY_FILE_DEST_SIZE` settings for each database to meet your retention target for each database: 30 GB for `database1`, 50 GB for `database2`, and 70 GB for `database3`.

Creating the Fast Recovery Area Disk Group

Procedure to create the fast recovery area disk group.

1. Go to the Oracle Grid Infrastructure home `bin` directory, and start Oracle ASM Configuration Assistant (ASMCA).

For example:

```
$ cd /u01/app/23.0.0/grid/bin
$ ./asmca
```

ASMCA opens the home window.

2. Click **Disk Groups** in the left panel to open the Disk Groups tab.
3. Click **Create** to create a new disk group.

The Create Disk Group window opens.

4. Provide configuration information for the fast recovery area as prompted:

In the Disk Group Name field, enter a descriptive name for the fast recovery area group.
For example: `FRA`.

In the Redundancy section, select the level of redundancy you want to use. For example:
`Normal`

In the Select Member Disks field, select eligible disks you want to add to the fast recovery area, and click **OK**. If you do not see the disks, click the **Change Disk Discovery Path** button and provide a path and pattern match for the disk. For example, `/dev/sd*` for local Oracle ASM disks and `n:/*/*` for NVMe over Fabrics disks.

5. When the Fast Recovery Area disk group creation is complete, click **Exit** and click **Yes** to confirm closing the Oracle ASMCA application.

Checking the SCAN Configuration

The Single Client Access Name (SCAN) is a name that is used to provide service access for clients to the cluster.

The SCAN makes it possible to add or remove nodes from the cluster without needing to reconfigure clients because the SCAN is associated with the cluster as a whole, rather than to a particular node.

The Single Client Access Name (SCAN) also adds location independence for the databases, so that client configuration does not have to depend on which nodes are running a particular database instance. Clients can continue to access the cluster in the same way as with previous releases, but Oracle recommends that clients accessing the cluster use the SCAN.

You can use the command `cluvfy comp scan` (located in *Grid home/bin*) to confirm that the DNS is correctly associating the SCAN with the addresses. For example:

```
$cluvfy comp scan
```

```
Verifying Single Client Access Name (SCAN) ...
```

```
  Verifying DNS/NIS name service 'rws127064-clu-scan.rws127064-
clu.rws12706410644.example.com' ...
```

```
    Verifying Name Service Switch Configuration File Integrity ...PASSED
```

```
Verifying DNS/NIS name service 'rws127064-clu-scan.rws127064-clu.rws12706410644.example.com' ...PASSED
Verifying Single Client Access Name (SCAN) ...PASSED
```

Verification of SCAN was successful.

```
CVU operation performed: SCAN
Date: Jul 29, 2016 1:42:41 AM
CVU home: /u01/crshome/
User: crsusr
```

After installation, when a client sends a request to the cluster, the Oracle Clusterware SCAN listeners redirect client requests to servers in the cluster.



See Also:

Oracle Clusterware Administration and Deployment Guide for more information about system checks and configurations

Setting Resource Limits for Oracle Clusterware and Associated Databases and Applications

After you have completed Oracle Grid Infrastructure installation, you can set resource limits in the `Grid_home/crs/install/s_crsconfig_nodename_env.txt` file.

The resource limits apply to all Oracle Clusterware processes and Oracle databases managed by Oracle Clusterware. For example, to set a higher number of processes limit, edit the file and set the `CRS_LIMIT_NPROC` parameter to a high value.

```
---
#Do not modify this file except as documented above or under the
#direction of Oracle Support Services.
#####
TZ=PST8PDT
NLS_LANG=AMERICAN_AMERICA.WE8ISO8859P1
CRS_LIMIT_STACK=2048
CRS_LIMIT_OPENFILE=65536
CRS_LIMIT_NPROC=65536
TNS_ADMIN=
```

About Changes in Default SGA Permissions for Oracle Database

By default, permissions to read and write to the System Global Area (SGA) are limited to the Oracle software installation owner.

In previous releases, both the Oracle installation owner account and members of the OSDBA group had access to shared memory. The change in Oracle Database 12c Release 2 (12.2) and later releases to restrict access by default to the Oracle installation owner account provides greater security than previous configurations. However, this change may prevent DBAs who do not have access to the Oracle installation owner account from administering the database.

The Oracle Database initialization parameter `ALLOW_GROUP_ACCESS_TO_SGA` determines if the Oracle Database installation owner account (`oracle` in Oracle documentation examples) is the only user who can read and write to the database System Global Area (SGA), or if members of the OSDBA group can read the SGA. In Oracle Database 12c Release 2 (12.2) and later releases, the default value for this parameter is `FALSE`, so that only the Oracle Database installation owner has read and write permissions to the SGA. Group access to the SGA is removed by default. This change affects all Linux and UNIX platforms.

If members of the OSDBA group require read access to the SGA, then you can change the initialization parameter `ALLOW_GROUP_ACCESS_TO_SGA` setting from `FALSE` to `TRUE`. Oracle strongly recommends that you accept the default permissions that limit access to the SGA to the `oracle` user account.

Related Topics

- [Oracle Database Reference](#)

Using Earlier Oracle Database Releases with Oracle Grid Infrastructure

Review these topics for information about using earlier Oracle Database releases with Oracle Grid Infrastructure 23ai installations.

- [General Restrictions for Using Earlier Oracle Database Releases](#)
Restrictions for using earlier Oracle Database releases with Oracle Grid Infrastructure 23ai.
- [Using ASMCA to Administer Disk Groups for Earlier Database Releases](#)
Use Oracle ASM Configuration Assistant (ASMCA) to create and modify disk groups when you install earlier Oracle databases and Oracle RAC databases on Oracle Grid Infrastructure installations.
- [Using the Correct LSNRCTL Commands](#)
To administer Oracle Database 23ai local and scan listeners using the `lsnrctl` command, set your `$ORACLE_HOME` environment variable to the path for the Oracle Grid Infrastructure home (Grid home).

General Restrictions for Using Earlier Oracle Database Releases

Restrictions for using earlier Oracle Database releases with Oracle Grid Infrastructure 23ai.

You can use Oracle Database 19c, Oracle Database 21c, and Oracle Database 23ai with Oracle Grid Infrastructure 23ai.

- Do not use the versions of `srvctl`, `lsnrctl`, or other Oracle Grid infrastructure home tools to administer earlier version databases. Administer earlier Oracle Database releases using the tools in the earlier Oracle Database homes. To ensure that the versions of the tools you are using are the correct tools for those earlier release databases, run the tools from the Oracle home of the database or object you are managing.
- You can store Oracle Database homes on Oracle Advanced Cluster File System (Oracle ACFS) only if the database version is Oracle Database 12c Release 2 (12.2) or later.

Using ASMCA to Administer Disk Groups for Earlier Database Releases

Use Oracle ASM Configuration Assistant (ASMCA) to create and modify disk groups when you install earlier Oracle databases and Oracle RAC databases on Oracle Grid Infrastructure installations.

Oracle ASM is installed as part of an Oracle Grid Infrastructure installation, with Oracle Clusterware. You can not use Oracle Database Configuration Assistant (Oracle DBCA) to perform administrative tasks on Oracle ASM.

See Also:

Oracle Automatic Storage Management Administrator's Guide for details about configuring disk group compatibility for databases with Oracle Grid Infrastructure 23ai.

Using the Correct LSNRCTL Commands

To administer Oracle Database 23ai local and scan listeners using the `lsnrctl` command, set your `$ORACLE_HOME` environment variable to the path for the Oracle Grid Infrastructure home (Grid home).

Do not attempt to use the `lsnrctl` commands from Oracle home locations for previous releases, as they cannot be used with the new release.

Relinking Oracle Grid Infrastructure for a Cluster Binaries

After installing Oracle Grid Infrastructure for a cluster, if you modify the Oracle Grid Infrastructure binaries, then you must relink the binaries on Oracle Linux 8 or earlier releases.

Note:

You do not need to relink the Oracle Clusterware and Oracle ASM binaries when you:

- Perform a fresh install of Oracle Grid Infrastructure on Oracle Linux 9 or later releases.
- Upgrade the operating system to Oracle Linux 9 or later releases.
- Apply any operating system patch to Oracle Linux 9 and later releases.

Caution:

Before relinking executables, you must shut down all executables that run in the Oracle home directory that you are relinking. In addition, shut down applications linked with Oracle shared libraries. If present, unmount all Oracle Advanced Cluster File System (Oracle ACFS) file systems.

1. As the `root` user, unlock the Oracle Grid Infrastructure home using the following command:

```
# cd Grid_home/crs/install
# rootcrs.sh -unlock
```

2. As the `grid` user, relink binaries using the following command:

```
$ export ORACLE_HOME=Grid_home
$ Grid_home/bin/relink
```

3. As the `root` user, relock the Grid home as follows:

```
# cd Grid_home/rdbms/install/
# ./rootadd_rdbms.sh
# cd Grid_home/crs/install
# rootcrs.sh -lock
```

You must relink the Oracle Clusterware and Oracle ASM binaries every time you apply an operating system patch or after you perform an operating system upgrade that does not replace the root file system.

13

Removing Oracle Database Software

Use the `deinstall` command that is included in Oracle homes to remove Oracle software. Oracle does not support the removal of individual products or components.

Caution:

If you have a single-instance database on a node in a cluster, and if you have multiple databases with the same global database name (GDN), then you cannot use the `deinstall` command to remove one database only.

- [About Oracle Deinstallation Options](#)
You can stop and remove Oracle Database software and components in an Oracle Database home with the `deinstall` command.
- [Oracle Deinstallation \(Deinstall\)](#)
You can run the `deinstall` command from an Oracle home directory after installation.
- [Unlocking and Deinstalling the Previous Release Grid Home](#)
- [Deinstallation Examples for Oracle Database](#)
Use these examples to help you understand how to run the `deinstall` command.
- [Deinstallation Response File Example for Oracle Grid Infrastructure for a Cluster](#)
You can run the `deinstall` command with the `-paramfile` option to use the values you specify in the response file.
- [Migrating Standalone Oracle Grid Infrastructure Servers to a Cluster](#)
Follow these steps to migrate an Oracle Database installation using Oracle Restart (that is, an Oracle Grid Infrastructure installation for a standalone server), to server as a cluster member node.
- [Changing the Oracle Grid Infrastructure Home Path](#)
After installing Oracle Grid Infrastructure for a cluster (Oracle Clusterware and Oracle ASM configured for a cluster), if you need to change the Grid home path, then use the following example as a guide to detach the old Grid home, and to attach a new Grid home:

About Oracle Deinstallation Options

You can stop and remove Oracle Database software and components in an Oracle Database home with the `deinstall` command.

You can remove the following software using `deinstall`:

- Oracle Database
- Oracle Grid Infrastructure, which includes Oracle Clusterware and Oracle Automatic Storage Management (Oracle ASM)
- Oracle Real Application Clusters (Oracle RAC)
- Oracle Database Client

The `deinstall` command is available in Oracle home directories after installation. It is located in the `$ORACLE_HOME/deinstall` directory.

`deinstall` creates a response file by using information in the Oracle home and using the information you provide. You can use a response file that you generated previously by running the `deinstall` command using the `-checkonly` option. You can also edit the response file template.

If you run `deinstall` to remove an Oracle Grid Infrastructure installation, then the deinstaller prompts you to run the `deinstall` command as the `root` user. For Oracle Grid Infrastructure for a cluster, the script is `rootcrs.sh`, and for Oracle Grid Infrastructure for a standalone server (Oracle Restart), the script is `roothas.sh`.

**Note:**

You must run the `deinstall` command from the same release to remove Oracle software. Do not run the `deinstall` command from a later release to remove Oracle software from an earlier release. For example, do not run the `deinstall` command from the 23ai Oracle home to remove Oracle software from an existing 19c Oracle home.

If the software in the Oracle home is not running (for example, after an unsuccessful installation), then `deinstall` cannot determine the configuration, and you must provide all the configuration details either interactively or in a response file.

In addition, before you run `deinstall` for Oracle Grid Infrastructure installations:

- Dismount Oracle Advanced Cluster File System (Oracle ACFS) and disable Oracle Automatic Storage Management Dynamic Volume Manager (Oracle ADVM).
- If Grid Naming Service (GNS) is in use, then notify your DNS administrator to delete the subdomain entry from the DNS.

Additional Files Deleted by deinstall

When you run `deinstall`, if the central inventory (`oraInventory`) contains no other registered homes besides the home that you are deconfiguring and removing, then `deinstall` removes the following files and directory contents in the Oracle base directory of the Oracle Database installation owner:

- `admin`
- `cfgtoollogs`
- `checkpoints`
- `diag`
- `oradata`
- `fast_recovery_area`

Oracle strongly recommends that you configure your installations using an Optimal Flexible Architecture (OFA) configuration, and that you reserve Oracle base and Oracle home paths for exclusive use of Oracle software. If you have any user data in these locations in the Oracle base that is owned by the user account that owns the Oracle software, then `deinstall` deletes this data.

 **Caution:**

- `deinstall` deletes Oracle Database configuration files, user data, and fast recovery area (FRA) files even if they are located outside of the Oracle base directory path.
- Do not manually remove files and directories in these locations as `deinstall` and the installer manage these directories. Be careful before placing files in these locations.

Oracle Deinstallation (Deinstall)

You can run the `deinstall` command from an Oracle home directory after installation.

Purpose

`deinstall` stops Oracle software, and removes Oracle software and configuration files on the operating system for a specific Oracle home.

Syntax

The `deinstall` command uses the following syntax:

```
(./deinstall [-silent] [-checkonly] [-paramfile complete path of input  
response file]  
[-params name1=value name2=value . . .]  
[-o complete path of directory for saving files]  
[-tmpdir complete path of temporary directory to use]  
[-logdir complete path of log directory to use] [-local] [-  
skipLocalHomeDeletion] [-skipRemoteHomeDeletion] [-help]
```

Parameters

Parameter	Description
-silent	<p>Use this flag to run <code>deinstall</code> in noninteractive mode. This option requires one of the following:</p> <ul style="list-style-type: none"> • A working system that it can access to determine the installation and configuration information. The <code>-silent</code> flag does not work with failed installations. • A response file that contains the configuration values for the Oracle home that is being deinstalled or deconfigured. <p>You can generate a response file to use or modify by running <code>deinstall</code> with the <code>-checkonly</code> flag. <code>deinstall</code> then discovers information from the Oracle home to deinstall and deconfigure. It generates the response file that you can then use with the <code>-silent</code> option.</p> <p>You can also modify the template file <code>deinstall.rsp.tmpl</code>, located in the <code>\$ORACLE_HOME/deinstall/response</code> directory.</p>
-checkonly	<p>Use this flag to check the status of the Oracle software home configuration. Running <code>deinstall</code> with the <code>-checkonly</code> flag does not remove the Oracle configuration. The <code>-checkonly</code> flag generates a response file that you can then use with the <code>deinstall</code> command and <code>-silent</code> option.</p>
-paramfile <i>complete path of input response file</i>	<p>Use this flag to run <code>deinstall</code> with a response file in a location other than the default. When you use this flag, provide the complete path where the response file is located.</p> <p>The default location of the response file is <code>\$ORACLE_HOME/deinstall/response</code>.</p>
-params [<i>name1=value name2=value name3=value ...</i>]	<p>Use this flag with a response file to override one or more values to change in a response file you have created.</p>
-o <i>complete path of directory for saving response files</i>	<p>Use this flag to provide a path other than the default location where the response file (<code>deinstall.rsp.tmpl</code>) is saved.</p> <p>The default location of the response file is <code>\$ORACLE_HOME/deinstall/response</code>.</p>
-tmpdir <i>complete path of temporary directory to use</i>	<p>Use this flag to specify a non-default location where <code>deinstall</code> writes the temporary files for the deinstallation.</p>
-logdir <i>complete path of log directory to use</i>	<p>Use this flag to specify a non-default location where <code>deinstall</code> writes the log files for the deinstallation.</p>

Parameter	Description
-local	Use this flag on a multinode environment to deinstall Oracle software in a cluster. When you run <code>deinstall</code> with this flag, it deconfigures and deinstalls the Oracle software on the local node (the node where <code>deinstall</code> is run). On remote nodes, it deconfigures Oracle software, but does not deinstall the Oracle software.
-skipLocalHomeDeletion	Use this flag in Oracle Grid Infrastructure installations on a multinode environment to deconfigure a local Grid home without deleting the Grid home.
-skipRemoteHomeDeletion	Use this flag in Oracle Grid Infrastructure installations on a multinode environment to deconfigure a remote Grid home without deleting the Grid home.
-help	Use this option to obtain additional information about the command option flags.

Unlocking and Deinstalling the Previous Release Grid Home

After upgrading from previous releases, if you want to deinstall the previous release Oracle Grid Infrastructure home, then you must first change the permission and ownership of the previous release Grid home.

1. As the `root` user, change the permission and ownership of the previous release Grid home using the following command syntax, where `oldGH` is the previous release Grid home, `giowner` is the Oracle Grid Infrastructure installation owner, and `oldGHParent` is the parent directory of the previous release Grid home:

```
#chmod -R 755 oldGH
#chown -R giowner oldGH
#chown giowner oldGHParent
```

For example:

```
#chmod -R 755 /u01/app/21.0.0/grid
#chown -R grid /u01/app/21.0.0/grid
#chown grid /u01/app/21.0.0/
```

2. As the `grid` user, and use the `-checkonly` parameter from previous release Grid home `oldGH/deinstall` directory to check the status of the Oracle software home configuration.

```
oldGH/deinstall/deinstall -checkonly -silent -o /tmp/ -tmpdir /tmp
```

3. Use the `deinstall` command from previous release Grid home `oldGH/deinstall` directory to deinstall the previous release Grid home.

```
oldGH/deinstall/deinstall -silent -tmpdir /tmp/rsp_file
```

4. As the `root` user, run the `rootdeinstall.sh` script from the `/tmp/deinstall<date>/` directory.

```
/tmp/deinstall<date>/rootdeinstall.sh
```

 **Caution:**

You must use the `deinstall` command from the same release to remove Oracle software. Do not run the `deinstall` command from a later release to remove Oracle software from an earlier release. For example, do not run the `deinstall` command from the 23.0.0.0.0 Oracle home to remove Oracle software from an existing 21.0.0.0.0 Oracle home.

Deinstallation Examples for Oracle Database

Use these examples to help you understand how to run the `deinstall` command.

Run `deinstall` from the `$ORACLE_HOME/deinstall` directory. The deinstallation starts without prompting you for the Oracle home path.

```
$ ./deinstall
```

You can generate a deinstallation response file by running `deinstall` with the `-checkonly` flag.

```
./deinstall -silent --checkonly
```

The `deinstall` tool generates a response file in `/tmp` and displays the location. For example, `/tmp/deinstall2024-08-01_01-40-28PM/response/deinstall_Ora23Home1.rsp`

Use the optional flag `-paramfile` to run this response file:

```
$ cd /u01/app/oracle/product/23.0.0/dbhome_1/deinstall
$ ./deinstall -paramfile /tmp/deinstall2024-08-01_01-40-28PM/response/
deinstall_Ora23Home1.rsp
```

Similarly, to remove the Oracle Grid Infrastructure home, use the `deinstall` command in the Oracle Grid Infrastructure home.

```
$ cd /u01/app/23.0.0/grid/deinstall
$ ./deinstall -paramfile /tmp/deinstall2024-08-01_01-40-28PM/response/
deinstall_Ora23Grid1.rsp
```

In this example, the Oracle Grid Infrastructure home is `/u01/app/23.0.0/grid`

Deinstallation Response File Example for Oracle Grid Infrastructure for a Cluster

You can run the `deinstall` command with the `-paramfile` option to use the values you specify in the response file.

Deinstallation Parameter File Description and Example

The following is an example of a response file for a cluster on nodes `node1` and `node2`, in which the Oracle Grid Infrastructure for a cluster software binary owner is `grid`, the Oracle Grid Infrastructure home (Grid home) is in the path `/u01/app/23.0.0/grid`, the Oracle base (the Oracle base for Oracle Grid Infrastructure, containing Oracle ASM log files, Oracle Clusterware logs, and other administrative files) is `/u01/app/grid/`, and the central Oracle Inventory home (`oraInventory`) is `/u01/app/oraInventory`. The local node (the node where you run the deinstallation session from) is `node1`:

```
# Copyright (c) 2005, 2020, Oracle and/or its affiliates. All rights reserved.
ORACLE_HOME=/u01/app/23.0.0/grid
CDATA_AUSIZE=1
BIG_CLUSTER=true
ISROLLING=true
LOCAL_NODE=node1
OCR_VD_DISKGROUPS="+DATA1"
ObaseCleanupPtrLoc=/tmp/deinstall2020-09-23_08-53-16AM/utl/orabase_cleanup.lst
CDATA_BACKUP_QUORUM_GROUPS=
ASM_CREDENTIALS=
EXTENDED_CLUSTER=false
SINGLE_NETWORK=false
LISTENER_USERNAME=aime
local=false
inventory_loc=/u01/app/oraInventory
ORACLE_HOME=/u01/app/23.0.0/grid
ASM_HOME=/u01/app/23.0.0/grid
ASM_DISK_GROUPS="+DATA1"
PING_TARGETS=
ORA_DBA_GROUP=oinstall
ASM_DISCOVERY_STRING=/dev/rdsd/*
CDATA_DISKS=/dev/rdsd/c0t600144F0C4A01A3F000056E6A12A0022d0s3, /dev/rdsd/
c0t600144F0C4A01A3F000056E6A12A0022d1s4
MinimumSupportedVersion=11.2.0.1.0
ORACLE_HOME_VERSION=23.0.0.0.0
ASM_DISKSTRING=/dev/rdsd/*
CDATA_QUORUM_GROUPS=
AHF_INSTALL_LOC=/opt/oracle.ahf
CRS_HOME=true
ODA_CONFIG=
USER_IGNORED_PREREQ=true
RHP_CONF=false
HAS_NOMULTICAST_ENV=
GNS_TYPE=
CRS_STORAGE_OPTION=1
CDATA_SITES=
```

```

CDATA_BACKUP_SIZE=0
GPNPGCONFIGDIR=$ORACLE_HOME
CDATA_DISK_GROUP=DATA1
LANGUAGE_ID=AMERICAN_AMERICA.AL32UTF8
CDATA_BACKUP_FAILURE_GROUPS=
RHP_PROVISIONED=
CRS_NODEVIPS='node1-v/255.255.252.0/eth0,node2-v/255.255.252.0/eth0'
ORACLE_OWNER=grid
GNS_ALLOW_NET_LIST=
silent=true
INSTALL_NODE=node1.example.com
ORACLE_HOME_VERSION_VALID=true
inst_group=oinstall
LOGDIR=/tmp/deinstall2020-09-23_08-53-16AM/logs
CDATA_EXC_VAULT=
EXTENDED_CLUSTER_SITES=crs-node
CDATA_REDUNDANCY=NORMAL
CDATA_BACKUP_DISK_GROUP=
APPLICATION_VIP=
GNS_DENY_ITF_LIST=
NODE_NAME_LIST=node1,node2
ORA_CRS_HOME=/u01/app/23.0.0/grid
ASM_LOCAL_SID=+ASM1
ORACLE_BASE=/u01/app/grid
GNS_CONF=false
CLUSTER_CLASS=STANDALONE
ORACLE_BINARY_OK=true
ASM_CONFIG=near
CDATA_BACKUP_REDUNDANCY=
CDATA_FAILURE_GROUPS=
OCR_LOCATIONS=
ASM_ORACLE_BASE=/u01/app/grid
GPNPCONFIGDIR=$ORACLE_HOME
ORA_ASM_GROUP=dba
GNS_CREDENTIALS=
CDATA_BACKUP_AUSIZE=1
GNS_DENY_NET_LIST=
OLD_CRS_HOME=
GNS_DOMAIN_LIST=
ASM_UPGRADE=false
NETCA_LISTENERS_REGISTERED_WITH_CRS=LISTENER
CDATA_BACKUP_DISKS=
ASMCA_ARGS=
CLUSTER_NODES=node1,node2
ASM_DIAGNOSTIC_DEST=/u01/app/grid
AFD_LABELS_NO_DG=
AFD_CONFIGURED=false
SCAN_PORT=1522
ASM_DROP_DISKGROUPS=true
OPC_NAT_ADDRESS=
CLUSTER_TYPE=DB
NETWORKS="eth0"/IP_Address:public,"eth1"/IP_Address:asm,"eth1"/
IP_Address:cluster_interconnect
OCR_VOTINGDISK_IN_ASM=true
CDATA_BACKUP_SITES=
CDATA_SIZE=0

```

```

REUSEDG=false
ASM_IN_HOME=true
ORACLE_SVCUSER=
HOME_TYPE=CRS
GNS_ADDR_LIST=
CLUSTER_NAME=node1-cluster
AFD_CONF=false
OPC_CLUSTER_TYPE=
VOTING_DISKS=
SILENT=true
SCAN_CREDENTIALS=
TZ=UTC
SCAN_TYPE=LOCAL
GPNP_PA=
DC_HOME=/tmp/deinstall2020-09-23_08-53-16AM/logs
CSS_LEASEDURATION=400
REMOTE_NODES=node2
ASM_SFILE=
AHF_REPOS_LOC=/u01/app/grid/data/repository
SCAN_NAME=node1-cluster-scan
RIM_NODE_LIST=
EXTENDED_CLUSTER_SITE_GUIDS=
INVENTORY_LOCATION=/u01/app/oraInventory
FASTDEPLOY_MODE=

```

 **Note:**

Do not use quotation marks with variables except in the following cases:

- Around addresses in *CRS_NODEVIPS*:

```
CRS_NODEVIPS='n1-vip/255.255.252.0/eth0,n2-vip/255.255.252.0/eth0'
```

- Around interface names in *NETWORKS*:

```
NETWORKS="eth0"/IP_Address:public,"eth1"/IP_Address:asm,"eth1"/
IP_Address:cluster_interconnect
```

Migrating Standalone Oracle Grid Infrastructure Servers to a Cluster

Follow these steps to migrate an Oracle Database installation using Oracle Restart (that is, an Oracle Grid Infrastructure installation for a standalone server), to server as a cluster member node.

1. List all the Oracle databases on the server with their version, unique name of the database, and Oracle home information:

```
$ srvctl config database -home
```

2. Inspect the Oracle Restart configuration of each database with `srvctl` using the following syntax, where `db_unique_name` is the unique name of the database, and `lsnrname` is the name of the listener:

```
$ srvctl config database -db db_unique_name
$ srvctl config service -db db_unique_name
$ srvctl config listener -listener lsnrname
$ srvctl config volume -volume volume_name -diskgroup diskgroup_name
```

Write down the configuration information for the server.

3. Stop all of the databases, services, and listeners that you discovered in step 1.
4. If present, unmount all Oracle Advanced Cluster File System (Oracle ACFS) file systems.
5. As the `root` user, unconfigure the Oracle Grid Infrastructure installation for a standalone server (Oracle Restart).

```
# cd /u01/app/23.0.0/grid/crs/install
# roothas.sh -deconfig -force
```

6. As the `root` user, open the `/etc/oratab` file and remove the entry corresponding to `oracle_restart_home`, in the following format:

```
# +ASM:oracle_restart_home:N
```

7. Prepare the server for Oracle Clusterware configuration, as described in this document. In addition, you can install Oracle Grid Infrastructure for a cluster in the same location as Oracle Restart, or in a different location.

Installing in the Same Location as Oracle Restart

- a. Unlock the Oracle Grid Infrastructure installation for a standalone server (Oracle Restart) home, using the following command:

```
# ./roothas.sh -unlock -hahome oracle_restart_home
```

- b. Proceed to step 7.

Installing in a Different Location than Oracle Restart

- a. Set up Oracle Grid Infrastructure software in the new Grid home software location as described in *Installing Only the Oracle Grid Infrastructure Software*.

- b. Proceed to step 7.

8. Set the environment variables as follows:

```
$ export oracle_install_asm_UseExistingDG=true or false
$ export oracle_install_asm_DiskGroupName=disk_group_name
$ export oracle_install_asm_DiskDiscoveryString=asm_discovery_string
```

If `oracle_install_asm_UseExistingDG` is set to `false`, then you do not need to specify other environment variables.

9. As the Oracle Grid Infrastructure installation owner, create and stage the response file for this installation as described in *Recording Response Files*.

10. Complete the installation in the silent mode using the following command:

```
$ /u01/app/23.0.0/grid/gridSetup.sh -silent -responseFile $ORACLE_HOME/
GI.rsp
```

11. Run the `root.sh` script.
12. Mount the Oracle ASM disk group used by Oracle Restart.
13. If you used Oracle ACFS with Oracle Restart, then:
- Start Oracle ASM Configuration Assistant (ASMCA). Run the `volenable` command to enable all Oracle Restart disk group volumes.
 - Mount all Oracle ACFS file systems manually.
14. Add back Oracle Clusterware services to the Oracle Clusterware home, using the information you wrote down in step 1, including adding back Oracle ACFS resources. For example:

```
$ /u01/app/23.0.0/grid/bin/srvctl add filesystem -device
/dev/asm/db1 -diskgroup ORestartData -volume db1 -mountpointpath
/u01/app/grid/product/23.0.0/db1 -user grid
```

15. Add the Oracle Database for support by Oracle Grid Infrastructure for a cluster, using the configuration information you recorded in step 1. Use the following command syntax, where `db_unique_name` is the unique name of the database on the node, and `nodename` is the name of the node:

```
$ srvctl add database -db db_unique_name -spfile spfile_name -pwfile
pwfile_name -oraclehome $ORACLE_HOME -node nodename
```

- For example, first verify that the `ORACLE_HOME` environment variable is set to the location of the database home directory.
- Next, to add the database name `mydb`, enter the following command:

```
$ srvctl add database -db mydb -spfile spfile_name -pwfile pwfile_name -
oraclehome $ORACLE_HOME -node node1
```

- Add each service to the database, using the command `srvctl add service`. For example, add `myservice` as follows:

```
$ srvctl add service -db mydb -service myservice -preferred myinstance
```

16. Add nodes to your cluster, as required, using the Oracle Grid Infrastructure installer.

See Also:

Oracle Clusterware Administration and Deployment Guide for information about adding nodes to your cluster.

Changing the Oracle Grid Infrastructure Home Path

After installing Oracle Grid Infrastructure for a cluster (Oracle Clusterware and Oracle ASM configured for a cluster), if you need to change the Grid home path, then use the following example as a guide to detach the old Grid home, and to attach a new Grid home:

Note:

Before changing the Grid home, you must shut down all executables that run in the Grid home directory that you are relinking. In addition, shut down applications linked with Oracle shared libraries.

1. As the `root` user, copy the Oracle Grid Infrastructure binaries from the old Grid home location to the new Grid home location. For example, where the old Grid home is `/u01/app/23.0.0/grid` and the new Grid home is `/u01/app/23ai/grid`.

```
# mkdir /u01/app/23ai/grid
# cp -pR /u01/app/23.0.0/grid /u01/app/23ai/grid
```

2. Change the owner and group for the directory and files in the new Grid home.

```
# chown -R grid:oinstall /u01/app/23ai/grid
```

3. As the `grid` user, run the `gridSetup.sh` command from the new Grid home directory and in the Select Configuration Option screen, select **Setup Software Only**.

```
$ /u01/app/23ai/grid/gridSetup.sh
```

Complete the installation by selecting the installation options as prompted. This step relinks the Oracle Grid Infrastructure binaries and updates the Oracle Inventory (`oraInventory`) with the new Oracle Grid Infrastructure home.

Note:

Do not change the Oracle base path during the installation.

4. As the `root` user, run the `root.sh` script from your new Grid home.

```
# /u01/app/23ai/grid/root.sh
```

5. As the `grid` user, enable Oracle RAC, dNFS, and `ioracle` from the new Grid home.

```
$ export ORACLE_HOME=/u01/app/23ai/grid
$ cd $ORACLE_HOME/rdbms/lib
$ make -f ins_rdbms.mk dnfs_on rac_on ioracle ORACLE_HOME=$ORACLE_HOME
```

6. As the `root` user, enter the following command to start up in the new home location.

```
# cd Grid_home/crs/install  
# ./rootcrs.sh -move -dstcrshome Grid_home
```

7. Repeat steps 1 through 8 on each cluster member node.

A

Oracle Grid Infrastructure Command-Line Options

Use this comprehensive list of Oracle Grid Infrastructure silent mode commands to install, configure, patch, upgrade, downgrade, and manage Oracle Grid Infrastructure deployments.

- [gridSetup.sh Command](#)
The `gridSetup.sh` command provides various flags that you can use without specifying any command option. If you do not provide any options, then `gridSetup.sh` starts the Oracle Grid Infrastructure installer.
- [gridSetup.sh -setupHome](#)
The `gridSetup.sh -setupHome` command installs the Oracle Grid Infrastructure software and registers the software with the Oracle central inventory.
- [gridSetup.sh -setupHomeAs](#)
The `gridSetup.sh -setupHomeAs` command installs the Oracle Grid Infrastructure software with Oracle base and privileged operating system groups identical to the specified grid home.
- [gridSetup.sh -configureCluster](#)
The `gridSetup.sh -configureCluster` command configures Oracle Grid Infrastructure for a Cluster software on the specified set of cluster nodes.
- [gridSetup.sh -switchGridhome](#)
The `gridSetup.sh -switchGridHome` command changes the active Oracle Grid Infrastructure home from the configured home to the current home from which you are running this command.
- [gridSetup.sh -upgrade](#)
The `gridSetup.sh -upgrade` command upgrades an earlier release Oracle Grid Infrastructure installation to the current release.
- [gridSetup.sh -downgrade](#)
The `gridSetup.sh -downgrade` command downgrades the Oracle Grid Infrastructure installation to an earlier release after a failed upgrade.
- [gridSetup.sh -createGoldImage](#)
The `gridSetup.sh -createGoldImage` command creates a gold image from the current Oracle Grid Infrastructure home.
- [gridSetup.sh -addNode](#)
The `gridSetup.sh -addNode` command adds a new node to your cluster.
- [gridSetup.sh -deleteNode](#)
The `gridSetup.sh -deleteNode` command removes the specified remote nodes from your cluster.

gridSetup.sh Command

The `gridSetup.sh` command provides various flags that you can use without specifying any command option. If you do not provide any options, then `gridSetup.sh` starts the Oracle Grid Infrastructure installer.

Syntax

```
gridSetup.sh [-silent [-ignorePrereqFailure]] [-responseFile
responsefilename] [-executePrereqs] [-executeConfigTools [-skipStackCheck]]
[-debug] [-applyOneOffs list_of_patch_directory_locations] [-nApplyOneOffs
directory_containing_multiple_patches]
[-executeRootScript -configMethod <ROOT | SUDO> [-sudoPath sudo_binary_path]
[-sudoUserName sudo_user_name]]]
```

Parameters

Table A-1 gridSetup.sh Flag Parameters

Parameter	Mandatory ?	Description
-silent	No	Run the installer in silent mode. You can either provide a response file path for inputs or a list of command line variable value pairs.
-ignorePrereqFailure	No	Specify this option to ignore all prerequisite checks failures.
-responseFile responsefilename	No	Absolute path of the response file, which has installation option values.
-executePrereqs	No	Run prerequisite checks to ensure that all necessary conditions and requirements are met before proceeding with the installation or configuration process.
-executeConfigTools	No	Run configuration tools for an installed Oracle Grid Infrastructure home. Note: You can use this parameter only with other commands, such as <code>gridSetup.sh -configureCluster</code> .
-skipStackCheck	No	Skip the Oracle Clusterware stack status check.
-debug	No	Run the Oracle Grid Infrastructure in the debug mode.
-applyOneOffs list_of_patch_directory_locations	No	Specify one or more paths to one-off patches to apply to the Oracle Grid Infrastructure home. You can pass multiple one-off patches as a comma separated list of locations.
-nApplyOneOffs directory_containing_multiple_patches	No	Specify a path to a location that contains multiple one-off patches to apply to the Oracle Grid Infrastructure home.
-executeRootScript	No	Specify this option to run the root script automatically. Note: You can use this parameter only with other commands such as <code>gridSetup.sh -configureCluster</code> .
-configMethod <ROOT SUDO>	No	Specify the configuration method to use for automatic root script execution. This can be either as the root user or as a sudo user.
-sudoPath sudo_binary_path	No	Absolute path of the sudo program binaries.
-sudoUserName sudo_user_name	No	Name of the user who is in the sudoers list and can run the root scripts.
-help	No	Displays the <code>gridSetup.sh</code> command help.

Example

The following example shows you how to install the Oracle Grid Infrastructure software using a response file.

```
gridSetup.sh -silent -ignorePrereqFailure -responseFile /u01/app/23.0.0/grid/
install/response/response_file.rsp
```

gridSetup.sh -setupHome

The `gridSetup.sh -setupHome` command installs the Oracle Grid Infrastructure software and registers the software with the Oracle central inventory.

Syntax

```
gridSetup.sh -setupHome -OSDBA sysdba_group -OSASM osasm_group -ORACLE_BASE
Oracle_base_dir
[-executePrereqs] [-OSOPER osoper_group] [-clusterNodes list_of_nodes] [-
INVENTORY_LOCATION central_inventory_location]
[-executeRootScript [-configMethod ROOT]
```

Parameters

Table A-2 gridSetup.sh -setupHome Command Parameters

Parameter	Mandatory ?	Description
-OSDBA <i>sysdba_group</i>	Yes	The name of the SYSDBA privileged operating system group. The default is dba.
-OSASM <i>osasm_group</i>	Yes	The name of the SYSASM privileged operating system group.
-ORACLE_BASE <i>Oracle_base_dir</i>	Yes	Complete path of the Oracle base location to use for the Oracle Grid Infrastructure installation.
-executePrereqs	No	Run prerequisite checks to ensure that all necessary conditions and requirements are met before proceeding with the installation or configuration process.
-OSOPER <i>osoper_group</i>	No	The name of the SYSOPER privileged operating system group.
-clusterNodes <i>list_of_nodes</i>	No	A comma-separated list of cluster nodes on which you want to install the Oracle Grid Infrastructure software.
-INVENTORY_LOCATION <i>central_inventory_location</i>	No	Complete path of the location where you want to store the inventory files. If you have previously installed an Oracle software on this system, then specify the existing inventory path.
-help	No	Displays the <code>gridSetup.sh -setupHome</code> command help.

Example

The following example shows you how to install Oracle Grid Infrastructure software on a three node cluster:

```
gridSetup.sh -setupHome -OSDBA sysdba -OSASM osasm -OSOPER osoper
-ORACLE_BASE /u01/app/grid -clusterNodes node1,node2,node3
-INVENTORY_LOCATION /u01/app/oraInventory -executeRootScript -configMethod
ROOT
```

gridSetup.sh -setupHomeAs

The `gridSetup.sh -setupHomeAs` command installs the Oracle Grid Infrastructure software with Oracle base and privileged operating system groups identical to the specified grid home.

Syntax

```
gridSetup.sh -setupHomeAs source_Oracle_home [-executePrereqs] [-OSDBA
sysdba_group]
[-OSASM osasm_group] [-OSOPER osoper_group] [-clusterNodes list_of_nodes]
[-ORACLE_BASE Oracle_base_dir] [-executeRootScript [-configMethod ROOT]]
```

Parameters

Table A-3 gridSetup.sh -setupHomeAs Command Parameters

Parameter	Mandatory ?	Description
<code>-executePrereqs</code>	No	Run prerequisite checks to ensure that all necessary conditions and requirements are met before proceeding with the installation or configuration process.
<code>-OSDBA sysdba_group</code>	No	The name of the SYSDBA privileged operating system group. The default is dba.
<code>-OSASM osasm_group</code>	No	The name of the SYSASM privileged operating system group.
<code>-OSOPER osoper_group</code>	No	The name of the SYSOPER privileged operating system group.
<code>-clusterNodes list_of_nodes</code>	No	A comma-separated list of cluster nodes on which you want to install the Oracle Grid Infrastructure software with Oracle base and privileged operating system groups identical to the specified source Oracle home.
<code>-ORACLE_BASE Oracle_base_dir</code>	No	Complete path to the Oracle base location to use for the Oracle Grid Infrastructure installation.
<code>-help</code>	No	Displays the <code>gridSetup.sh -setupHomeAs</code> command help.

Example

The following example shows how to setup a Grid home identical to the specified source Grid home, on a three node cluster:

```
gridSetup.sh -setupHomeAs /u01/app/23.0.0/grid -clusterNodes node4,node5
-OSDBA sysdba -OSASM osasm -OSOPER osoper -ORACLE_BASE /u01/app/grid -
clusterNodes node1,node2,node3 -executeRootScript -configMethod ROOT
```

gridSetup.sh -configureCluster

The `gridSetup.sh -configureCluster` command configures Oracle Grid Infrastructure for a Cluster software on the specified set of cluster nodes.

Syntax

```
gridSetup.sh -configureCluster -OSDBA sysdba_group -OSASM osasm_group -
ORACLE_BASE Oracle_base_dir
-clusterName cluster_name -networkInterfaceList
interface_name_with_usage_value
[-executePrereqs] [-OSOPER osoper_group] [-clusterUsage <RAC |
GENERAL_PURPOSE>] [-configureAsExtendedCluster -sites site_names]
{[-scanName scan_name -scanPort scan_port]} | [-scanClientDataFile
client_data_file_path]}
[-configureGNS -gnsVIPAddress GNS_VIP -gnsSubDomain GNS_subdomain [-
configureDHCPAssignedVIPs]] [-clusterNodes list_of_node_names]
[-storageOption <FLEX_ASM_STORAGE | CLIENT_ASM_STORAGE | FILE_SYSTEM_STORAGE>]
{[-diskGroupName disk_group_name {-diskList list_of_disks |
-disksWithFailureGroupNames failure_group_disk_names -failureGroups
failure_group_names -quorumFailureGroupNames quorum_failure_groups}
[-redundancy <NORMAL | HIGH | EXTERNAL | FLEX | EXTENDED>] [-auSize <1 | 2 |
4 | 8 | 16>] [-diskString disk_discovery_string] [-configureAFD]
[-backupDGName OCR_backup_disk_group_name {-backupDGDiskList
backup_DG_disk_list | -backupDGDisksWithFailureGroupNames
-backupDGFailureGroups backup_DG_failure_group_name -
backupDGQuorumFailureGroups backup_quorum_failure_groups}}]
| [-clientDataFile client_data_file] | [-ocrLocations OCR_file_location -
votingFilesLocations voting_file_location}}]
[-enableAutoFixup] [-useIPMI -bmcBinpath BMC_binary_loc -bmcUsername
BMC_user_name] [-managementOption <CLOUD_CONTROL | NONE> -omsHost EM_hostname
-omsPort EM_port -emAdminUser EM_admin_username] [-INVENTORY_LOCATION
central_inventory_location]
[-executeConfigTools] [-executeRootScript -configMethod ROOT]
```

Parameters

Table A-4 gridSetup.sh -configureCluster Command Parameters

Parameter	Mandatory ?	Description
-OSDBA <i>sysdba_group</i>	Yes	The name of the SYSDBA privileged operating system group. The default is dba. Note: If you have already setup an Oracle Grid Infrastructure home, then this parameter is not required.
-OSASM <i>osasm_group</i>	Yes	The name of the SYSASM privileged operating system group. Note: If you have already setup an Oracle Grid Infrastructure home, then this parameter is not required.
-ORACLE_BASE <i>Oracle_base_dir</i>	Yes	Complete path to the Oracle base location to use for the Oracle Grid Infrastructure installation. Note: If you have already setup an Oracle Grid Infrastructure home, then this parameter is not required.
-clusterName <i>cluster_name</i>	Yes	Name for the cluster that you are creating.
- networkInterfaceList <i>interface_name_with _usage_value</i>	Yes	Planned use for each network adapter (or network interface) that are available on your cluster node.
-OSOPER <i>osoper_group</i>	No	The name of the SYSOPER privileged operating system group. Note: If you have already setup an Oracle Grid Infrastructure home, then this parameter is not required.
-executePrereqs	No	Run prerequisite checks to ensure that all necessary conditions and requirements are met before proceeding with the installation or configuration process.
-clusterUsage <RAC GENERAL_PURPOSE>	No	Usage for the cluster, which can be to host Oracle Real Application Clusters (Oracle RAC) database or to host generic applications. The default value is RAC.
- configureAsExtended Cluster [-sites <i>site_names</i>]	No	Extend an Oracle RAC cluster across two or more separate sites, each equipped with its own storage. If you are configuring an Extended Cluster, then specify the list of sites.
-scanName {- scanPort <i>scan_port</i> }	No	Name for the Single Client Access Name (SCAN) and an unused port number for the SCAN service to create a SCAN locally.
-scanClientDataFile <i>client_data_file_path</i>	No	Complete path to the SCAN client data file to use a shared SCAN.
-configureGNS	No	Specify this option if you want to configure Grid Naming Service (GNS).
-gnsVIPAddress <i>GNS_VIP</i> {- gnsSubDomain <i>GNS_subdomain</i> }	No	An unused virtual hostname and GNS subdomain for the GNS service.

Table A-4 (Cont.) gridSetup.sh -configureCluster Command Parameters

Parameter	Mandatory ?	Description
-configureDHCPAssignedVIPs	No	Specify this option if you want to assign SCAN name VIP and Node VIPs by DHCP.
-clusterNodes <i>list_of_node_names</i>	No	A comma-separated list of cluster nodes on which you want to install the Oracle Grid Infrastructure software.
-storageOption <FLEX_ASM_STORAGE CLIENT_ASM_STORAGE FILE_SYSTEM_STORAGE >	No	Storage to use for Oracle Cluster Registry (OCR) and Voting Files. Default value is FLEX_ASM_STORAGE. <ul style="list-style-type: none"> Use FLEX_ASM_STORAGE to store OCR and voting files on an Oracle ASM disk group. Use CLIENT_ASM_STORAGE to store OCR and voting files on an Oracle ASM disk group configured on a storage server cluster. Use FILE_SYSTEM_STORAGE to store OCR and voting files on a shared file system.
-diskGroupName <i>disk_group_name</i>	No	Name for the Oracle ASM disk group, for example DATA.
-diskList <i>list_of_disks</i>	No	A list of Oracle ASM disks to create an Oracle ASM disk group. Note: Use this variable only if failure group configuration is not required.
-disksWithFailureGroupNames <i>failure_group_disk_names</i> {- failureGroups <i>failure_group_names</i> - quorumFailureGroupNames <i>quorum_failure_groups</i> }	No	A list of failure groups to be marked as QUORUM. A quorum failure group, a special type of failure group, contains mirror copies of voting files when voting files are stored in normal or high redundancy disk groups.
-redundancy <NORMAL HIGH EXTERNAL FLEX EXTENDED>	No	The Oracle ASM redundancy level to use for the Oracle ASM disk group. Default value is NORMAL.
-auSize <1 2 4 8 16>	No	The allocation unit size for Oracle ASM. Default value is 1.
-diskString <i>disk_discovery_string</i>	No	Disk discovery string, a path and pattern match for the Oracle ASM disks, to discover the disks for creating an Oracle ASM disk group.
-configureAFD	No	Specify this option if you want to configure Oracle ASM Filter Driver (Oracle ASMFDF).
-backupDGName <i>OCR_backup_disk_group_name</i>	No	Name for the OCR backup Oracle ASM disk group.
-backupDGDiskList <i>backup_DG_disk_list</i>	No	A list of Oracle ASM disks to create an OCR backup Oracle ASM disk group. Note: Use this variable only if failure group configuration is not required.

Table A-4 (Cont.) gridSetup.sh -configureCluster Command Parameters

Parameter	Mandatory ?	Description
- backupDGDisksWithFailureGroupNames {- backupDGFailureGroups <i>backup_DG_failure_group_name</i> - backupDGQuorumFailureGroups <i>backup_quorum_failure_groups</i> }	No	A list of failure groups to be marked as QUORUM. A quorum failure group, a special type of failure group, contains mirror copies of OCR when OCR is stored in normal or high redundancy disk groups.
-clientDataFile <i>client_data_file</i>	No	Complete path to the Oracle ASM client data file if you are using Oracle ASM disk group configured on a storage server cluster.
-ocrLocations <i>OCR_file_location</i> {- votingFilesLocations <i>voting_file_location</i> }	No	Storage option for Oracle Cluster Registry (OCR) and voting files.
-enableAutoFixup	No	Specify this option if you want to configure automatic self correction for your installation. The automated fixup framework for Configuration Verification Utility (CVU) identifies and corrects any configuration errors.
-useIPMI	No	Specify this option if you want to configure Intelligent Power Management Interface (IPMI).
-bmcBinpath <i>BMC_binary_loc</i>	No	Location of the ipmiutil binary.
-bmcUsername <i>BMC_user_name</i>	No	Username for using the IPMI service.
-managementOption <CLOUD_CONTROL NONE>	No	Management option to use for managing the Oracle home. Default value is NONE.
-omsHost <i>EM_hostname</i>	No	The OMS host to connect to Enterprise Manager Cloud Control.
-omsPort <i>EM_port</i>	No	The OMS port to connect to Enterprise Manager Cloud Control.
-emAdminUser <i>EM_admin_username</i>	No	The Admin username to connect to Enterprise Manager Cloud Control.
- INVENTORY_LOCATION <i>entral_inventory_location</i>	No	Complete path to the location where you want to store the inventory files. You do not need to specify this parameter if you have previously installed an Oracle software on this computer.
-help	No	Displays <code>gridSetup.sh -configureCluster</code> command help.

Example

The following example shows you how to install and configure Oracle Grid Infrastructure on a three node cluster:

```
gridSetup.sh -configureCluster -OSDBA sysdba -OSASM osasm -
ORACLE_BASE /u01/app/grid -clusterName mycluster1
-networkInterfaceList
ens3:100.70.80.0:1,ens4:192.168.1.0:5,ens5:192.168.2.0:3 -OSOPER osoper -
clusterUsage RAC -scanName RACScan -scanPort 1521
-clusterNodes node1,node2,node3 -storageOption FLEX_ASM_STORAGE -
diskGroupName DATA -diskList /dev/sd1,/dev/sd2,/dev/sd3 -redundancy NORMAL
-auSize 8 -diskString /dev/sd* -configureAFD -backupDGName RECO -
backupDGDiskList /dev/bk1,/dev/bk2,/dev/bk3 -enableAutoFixup
-managementOption NONE -INVENTORY_LOCATION /u01/app/oraInventory -
executeConfigTools -executeRootScript -configMethod ROOT
```

gridSetup.sh -switchGridhome

The `gridSetup.sh -switchGridHome` command changes the active Oracle Grid Infrastructure home from the configured home to the current home from which you are running this command.

Syntax

```
gridSetup.sh -switchGridHome [-zeroDowntimeGIPatching [-skipDriverUpdate]]
[-rollback -oldHome old_GI_Home [-clusterNodes list_of_nodes]]
[-executePrereqs] [-drainTimeoutInSeconds number_of_seconds] [-resume]
```

Parameters

Table A-5 gridSetup.sh -switchGridHome Command Parameters

Parameter	Mandatory ?	Description
-zeroDowntimeGIPatching	No	Switch the active Oracle Grid Infrastructure home to the current home without stopping the databases and services.
-skipDriverUpdate	No	Specify this option to skip updating the operating system drivers, such as Oracle ACFS and Oracle ASMFd. Note: If the patch that you are installing contains operating system driver updates, then you must use <code>-skipDriverUpdate</code> to avoid restarting your server.
-rollback {-oldHome <i>old_GI_Home</i> -clusterNodes <i>list_of_nodes</i> }	No	Switch back to the previous Oracle Grid Infrastructure home when the patching operation fails. When you use this option, specify the old Grid Infrastructure home and the list of cluster nodes on which you want to perform the rollback operation.
-executePrereqs	No	Run prerequisite checks to ensure that all necessary conditions and requirements are met before proceeding with the installation or configuration process.

Table A-5 (Cont.) gridSetup.sh -switchGridHome Command Parameters

Parameter	Mandatory ?	Description
- drainTimeoutInSeconds <i>number_of_seconds</i>	No	Drain the database services before stopping the database instances on the current node. Specify the drain timeout value in seconds.
-resume	No	Resume operation to run pending and failed jobs.
-help	No	Displays the <code>gridSetup.sh -switchGridhome</code> command help.

Usage Notes

You cannot use the `-zeroDowntimeGIPatching` and `-rollback` options together.

Example

The following example shows how to switch from the current Grid home to the patched Grid home.

```
gridSetup.sh -switchGridHome -zeroDowntimeGIPatching -skipDriverUpdate -
drainTimeoutInSeconds 60
```

Related Topics

-

gridSetup.sh -upgrade

The `gridSetup.sh -upgrade` command upgrades an earlier release Oracle Grid Infrastructure installation to the current release.

Syntax

```
gridSetup.sh -upgrade [-executePrereqs] [-ORACLE_BASE oracle_base_dir] [-
dryRun] [-batchInfo batch_map]
[-ignoreDownNodes] [-executeConfigTools] [-executeRootScript -configMethod
ROOT]]
```

Parameters**Table A-6 gridSetup.sh -upgrade Command Parameters**

Parameter	Mandatory ?	Description
-executePrereqs	No	Run prerequisite checks to ensure that all necessary conditions and requirements are met before proceeding with the installation or configuration process.
-ORACLE_BASE <i>oracle_base_dir</i>	No	Complete path to the Oracle base location to use for the Oracle Grid Infrastructure upgrade.

Table A-6 (Cont.) gridSetup.sh -upgrade Command Parameters

Parameter	Mandatory ?	Description
-dryRun	No	Perform a dry-run of the Oracle Grid Infrastructure upgrade process to check readiness for the upgrades.
-batchInfo <i>batch_map</i>	No	Specify the cluster nodes batch map.
-ignoreDownNodes	No	Skip upgrading the cluster nodes that are down during the Oracle Grid Infrastructure upgrade operation.
-help	No	Displays <code>gridSetup.sh -upgrade</code> command help.

Example

The following example shows you how to upgrade Oracle Grid Infrastructure to 23ai:

```
gridSetup.sh -upgrade -ORACLE_BASE /u01/app/grid [-ignoreDownNodes] -
executeConfigTools -executeRootScript -configMethod ROOT
```

Related Topics

- [Restrictions for Oracle Grid Infrastructure Upgrades](#)
Restrictions and changes for upgrades to Oracle Clusterware installations, which consists of Oracle Grid Infrastructure and Oracle Automatic Storage Management (Oracle ASM).
- [Preparing to Upgrade an Existing Oracle Clusterware Installation](#)
If you have an existing Oracle Clusterware installation, then you upgrade your existing cluster by performing an out-of-place upgrade. You cannot perform an in-place upgrade.

gridSetup.sh -downgrade

The `gridSetup.sh -downgrade` command downgrades the Oracle Grid Infrastructure installation to an earlier release after a failed upgrade.

Syntax

```
gridSetup.sh -downgrade -oldHome old_GI_home_to_downgrade
[-executeConfigTools] [-executeRootScript -configMethod ROOT]
```

Parameters**Table A-7 gridSetup.sh -downgrade Command Parameters**

Parameter	Mandatory ?	Description
-oldHome <i>old_GI_home_to_downgrade</i>	Yes	Earlier release Oracle Grid Infrastructure home to which you want to downgrade.
-help	No	Displays <code>gridSetup.sh -downgrade</code> command help.

Example

The following example shows you how to downgrade Oracle Grid Infrastructure to an earlier release, from which you upgraded:

```
gridSetup.sh -downgrade -oldHome /u01/app/21.6.0/grid -executeConfigTools -  
executeRootScript -configMethod ROOT
```

Related Topics

- [Restrictions for Oracle Grid Infrastructure Downgrades](#)
Review the following information for restrictions and changes for downgrading Oracle Grid Infrastructure installations.
- [Downgrading Oracle Grid Infrastructure](#)
Use this procedure to downgrade Oracle Grid Infrastructure after a successful upgrade.

gridSetup.sh -createGoldImage

The `gridSetup.sh -createGoldImage` command creates a gold image from the current Oracle Grid Infrastructure home.

Syntax

```
gridSetup.sh -createGoldImage -destinationLocation  
directory_to_store_gold_image [-exclFiles file_paths]
```

Parameters

Table A-8 gridSetup.sh -createGoldImage Command Parameters

Parameter	Mandatory ?	Description
- destinationLocation directory_to_store_ gold_image	Yes	Specify the complete path, or location, where you want to store the gold images.
-exclFiles file_paths	No	Specify the complete paths to the files to be excluded from the newly created gold image.
-help	No	Displays the <code>gridSetup.sh -createGoldImage</code> command help.

Example

The following example shows how to create a gold image at the specified location:

```
gridSetup.sh -createGoldImage -destinationLocation /tmp/my_grid_images
```

gridSetup.sh -addNode

The `gridSetup.sh -addNode` command adds a new node to your cluster.

Syntax

```
gridSetup.sh -addNode -clusterNodes list_of_nodes_to_add [-executePrereqs] [-executeRootScript -configMethod <ROOT | SUDO>]
```

Parameters

Table A-9 gridSetup.sh -addNode Command Parameters

Parameter	Mandatory ?	Description
-clusterNodes <i>list_of_nodes_to_add</i>	Yes	Names of the new cluster nodes that you want to add to your cluster.
-executePrereqs	No	Run prerequisite checks to ensure that all necessary conditions and requirements are met before proceeding with the installation or configuration process.
-executeRootScript	No	Specify this option to run the root script automatically.
-configMethod <ROOT SUDO>	No	Specify the configuration method to use for automatic root script execution. This can be either as the <code>root</code> user or as a <code>sudo</code> user.
-help	No	Displays <code>gridSetup.sh -addNode</code> command help.

Usage Notes

The new cluster node name must be unique throughout the cluster.

Example

To add two new nodes, `node3` and `node4` to an existing cluster.

```
gridSetup.sh -addNode -clusterNodes node3,node4
```

gridSetup.sh -deleteNode

The `gridSetup.sh -deleteNode` command removes the specified remote nodes from your cluster.

Syntax

```
gridSetup.sh -deleteNode -nodesToDelete list_of_nodes_to_delete
```

Parameters

Table A-10 gridSetup.sh -deleteNode Command Parameters

Parameter	Mandatory ?	Description
-nodesToDelete <i>list_of_nodes_to_delete</i>	Yes	Names of the remote cluster nodes that you want to delete from your cluster.

Table A-10 (Cont.) gridSetup.sh -deleteNode Command Parameters

Parameter	Mandatory ?	Description
-help	No	Displays gridSetup.sh -deleteNode command help.

Usage Notes

You can delete only the remote nodes, not the local node.

 **See Also:****Example**

```
gridSetup.sh -deleteNode -nodesToDelete node3
```

B

Response Files

Review the following topics to install and configure Oracle Database, Oracle Grid Infrastructure, and other Oracle products using response files.

- [Reasons for Using Silent Mode or Response File Mode](#)
Review this section for use cases for running the installer in silent mode or response file mode.
- [Using Response Files](#)
Use response files to install and configure Oracle products using the installer in silent or response file mode.
- [Preparing Response Files](#)
Review this information to prepare response files for use during silent mode or response file mode installations.
- [Running Oracle Universal Installer Using a Response File](#)
After creating the response file, run Oracle Universal Installer at the command line, specifying the response file you created, to perform the installation.
- [Postinstallation Configuration Using Response File Created During Installation](#)
Use response files to configure Oracle software after installation. You can use the same response file created during installation to also complete postinstallation configuration.

Reasons for Using Silent Mode or Response File Mode

Review this section for use cases for running the installer in silent mode or response file mode.

Mode	Uses
Silent	<p>Use silent mode for the following installations:</p> <ul style="list-style-type: none">• Complete an unattended installation, which you schedule using operating system utilities such as <code>at</code>.• Complete several similar installations on multiple systems without user interaction.• Install the software on a system that does not have X Window System software installed on it. <p>The installer displays progress information on the terminal that you used to start it, but it does not display any of the installer screens.</p>
Response file	<p>Use response file mode to complete similar Oracle software installations on more than one system, providing default answers to some, but not all of the installer prompts.</p>

Using Response Files

Use response files to install and configure Oracle products using the installer in silent or response file mode.



Note:

You must complete all required preinstallation tasks on a system before running the installer in silent or response file mode.

1. Prepare a response file.
2. Run the installer in silent or response file mode.
3. Run the root scripts as prompted by Oracle Universal Installer.
4. If you completed a software-only installation, then run Net Configuration Assistant and Oracle DBCA in silent or response file mode to create the database listener and an Oracle Database instance respectively.

Preparing Response Files

Review this information to prepare response files for use during silent mode or response file mode installations.

- [Editing a Response File Template](#)
Oracle provides response file templates for each product and each configuration tool.
- [Recording Response Files](#)
You can use OUI in interactive mode to record response files, which you can then edit and use to complete silent mode or response file mode installations.

Editing a Response File Template

Oracle provides response file templates for each product and each configuration tool.

About Response File Templates

For Oracle Database, the response file templates are located in the `$ORACLE_HOME/install/response` directory. For Oracle Grid Infrastructure, the response file templates are located in the `Grid_home/install/response` directory.

Where, *Grid_home* is the Oracle Grid Infrastructure home directory path.



Note:

If you copied the software to a hard disk, then the response files are located in the `$ORACLE_HOME/install/response` directory.

All response file templates contain comment entries, sample formats, examples, and other useful instructions. Read the response file instructions to understand how to specify values for the response file variables, so that you can customize your installation.

The following table lists the response files provided with this software:

Table B-1 Response Files for Oracle Database and Oracle Grid Infrastructure

Response File	Description
db_install.rsp	Silent installation of Oracle Database.
dbca.rsp	Silent creation and configuration of Oracle Database using Oracle DBCA.
netca.rsp	Silent configuration of Oracle Net using Oracle NETCA.
gridsetup.rsp	Silent configuration of Oracle Grid Infrastructure installations.

 **Caution:**

When you modify a response file template and save a file for use, the response file may contain plain text passwords. Ownership of the response file should be given to the Oracle software installation owner only, and permissions on the response file should be changed to 600. Oracle strongly recommends that database administrators or other administrators delete or secure response files when they are not in use.

To copy and modify a response file:

1. Copy the response file from the response file directory to a directory on your system:

For example, for Oracle Database:

```
$ cp $ORACLE_HOME/install/response/db_install.rsp local_directory
```

2. Open the response file in a text editor:

```
$ vi /local_directory/db_install.rsp
```

3. Follow the instructions in the file to edit it.

 **Note:**

The installer or configuration assistant fails if you do not correctly configure the response file. Also, ensure that your response file name has the `.rsp` suffix.

4. Secure the response file by changing the permissions on the file to 600:

```
$ chmod 600 /local_dir/db_install.rsp
```

Ensure that only the Oracle software owner user can view or modify response files or consider deleting them after the installation succeeds.

 **Note:**

A fully-specified response file for an Oracle Database installation contains the passwords for database administrative accounts and for a user who is a member of the OSDBA group (required for automated backups).

Recording Response Files

You can use OUI in interactive mode to record response files, which you can then edit and use to complete silent mode or response file mode installations.

Recording response files is useful for Advanced or software-only installations. You can save all the installation steps into a response file during installation by clicking **Save Response File** on the **Summary** page. You can use the generated response file for a silent installation later. When you record the response file, you can either complete the installation, or you can exit from the installer on the Summary page, before OUI starts to set up the software to the system.

If you use record mode during a response file mode installation, then the installer records the variable values that were specified in the original source response file into the new response file.

 **Note:**

OUI does not save passwords while recording the response file.

1. Complete preinstallation tasks as for a standard installation.

When you run the installer to record a response file, it checks the system to verify that it meets the requirements to install the software. For this reason, Oracle recommends that you complete all of the required preinstallation tasks and record the response file while completing an installation.

2. Ensure that the Oracle software owner user (typically `oracle`) has permissions to create or write to the Oracle home path that you specify when you run the installer.
3. On each installation screen, specify the required information.
4. When the installer displays the **Summary** screen, perform the following steps:
 - a. Click **Save Response File**. In the window, specify a file name and location for the new response file. Click **Save** to write the responses you entered to the response file.
 - b. Click **Finish** to continue with the installation. Click **Cancel** if you do not want to continue with the installation. The installation stops, but the recorded response file is retained.

 **Note:**

Ensure that your response file name has the `.rsp` suffix.

5. Before you use the saved response file on another system, edit the file and make any required changes. Use the instructions in the file as a guide when editing it.

Running Oracle Universal Installer Using a Response File

After creating the response file, run Oracle Universal Installer at the command line, specifying the response file you created, to perform the installation.

Run Oracle Universal Installer at the command line, specifying the response file you created. The Oracle Universal Installer executables, `runInstaller` and `gridSetup.sh`, provide several options. For help information on the full set of these options, run the `gridSetup.sh` or `runInstaller` command with the `-help` option. For example:

- For Oracle Database:

```
$ $ORACLE_HOME/runInstaller -help
```

- For Oracle Grid Infrastructure:

```
$ /u01/app/23.0.0/grid/gridSetup.sh -help
```

The help information appears in a window after some time.

Perform the following steps to run the installer using a response file:

1. Complete the preinstallation tasks for a normal installation.
2. Log in as the software installation owner user.
3. If you are completing a response file mode installation, then set the operating system `DISPLAY` environment variable for the user running the installation.

Note:

You do not have to set the `DISPLAY` environment variable if you are completing a silent mode installation.

4. To start the installer in silent or response file mode, enter a command similar to the following:

- For Oracle Database:

```
$ $ORACLE_HOME/runInstaller [-silent] -responseFile responsefilename
```

- For Oracle Grid Infrastructure:

```
$ /u01/app/23.0.0/grid/gridSetup.sh [-silent] -responseFile  
responsefilename
```

Note:

Do not specify a relative path to the response file. If you specify a relative path, then the installer fails.

In this example:

- `-silent` runs the installer in silent mode.
 - `responsefilename` is the full path and file name of the installation response file that you configured.
5. If this is the first time you are installing Oracle software on your system, then Oracle Universal Installer prompts you to run the `oraInstRoot.sh` script. Log in as the `root` user and run the `oraInstRoot.sh` script:

```
$ su root
password:
# /u01/app/oraInventory/oraInstRoot.sh
```

Note:

You do not have to manually create the `oraInst.loc` file. Running the `oraInstRoot.sh` script is sufficient as it specifies the location of the Oracle Inventory directory.

6. When the installation completes, log in as the `root` user and run the `root.sh` script. For example:

```
$ su root
password:
# $ORACLE_HOME/root.sh
```

Postinstallation Configuration Using Response File Created During Installation

Use response files to configure Oracle software after installation. You can use the same response file created during installation to also complete postinstallation configuration.

- [Using the Installation Response File for Postinstallation Configuration](#)
You can use the response file created during installation to also complete postinstallation configuration.
- [Running Postinstallation Configuration Using Response File](#)
You can use a response file to complete postinstallation tasks on one or more servers simultaneously.

Using the Installation Response File for Postinstallation Configuration

You can use the response file created during installation to also complete postinstallation configuration.

Run the installer with the `-executeConfigTools` option to configure configuration assistants after installing Oracle Grid Infrastructure or Oracle Database. You can use the response file located at `$ORACLE_HOME/install/response/product_timestamp.rsp` to obtain the passwords required to run the configuration tools. You must update the response file with the required passwords before running the `-executeConfigTools` command.

Oracle strongly recommends that you maintain security with a password response file:

- Permissions on the response file should be set to 600.
- The owner of the response file should be the installation owner user, with the group set to the central inventory (`oraInventory`) group.

Example B-1 Response File Passwords for Oracle Grid Infrastructure (`grid` user)

```
bmcPassword=password
sysasmPassword=password
asmsnmpPassword=password
emadminPassword=password
```

If you do not have a BMC card, or you do not want to enable IPMI, then leave the `ipmi.bmcPassword` input field blank.

If you do not want to enable Oracle Enterprise Manager for management, then leave the `emAdminPassword` password field blank.

Example B-2 Response File Passwords for Oracle Grid Infrastructure for a Standalone Server (`oracle` user)

```
sysasmPassword=password
asmsnmpPassword=password
emadminPassword=password
```

If you do not want to enable Oracle Enterprise Manager for management, then leave the `emAdminPassword` password field blank.

Example B-3 Response File Passwords for Oracle Database (`oracle` user)

This example illustrates the passwords to specify for use with the database configuration assistants.

```
sysPassword=password
systemPassword=password
dbsnmpPassword=password
pdbadminPassword=password
emAdminPassword=password
asmsnmpPassword=password
```

You can also specify `allPassword=password` to use the same password for all database users.

The database configuration assistants require the SYS, SYSTEM, PDBADMIN, and DBSNMP passwords for use with Oracle DBCA. You must specify the following passwords, depending on your system configuration:

- If the database uses Oracle Automatic Storage Management (Oracle ASM) for storage, then you must specify a password for the `ASMSNMPPassword` variable. If you are not using Oracle ASM, then leave the value for this password variable blank.

Running Postinstallation Configuration Using Response File

You can use a response file to complete postinstallation tasks on one or more servers simultaneously.

Complete this procedure to run configuration assistants with the `executeConfigTools` command and a response file.

1. Edit the response file and specify the required passwords for your configuration. You can use the response file created during installation, located at `$ORACLE_HOME/install/response/product_timestamp.rsp`.

2. Change directory to the Oracle home containing the installation software. For example:

For Oracle Grid Infrastructure:

```
cd Grid_home
```

Where, *Grid_home* is the path to the Oracle Grid Infrastructure home directory `/u01/app/23.0.0/grid`

For Oracle Database:

```
cd $ORACLE_HOME
```

3. Run the configuration script using the following syntax:

For Oracle Grid Infrastructure:

```
$ ./gridSetup.sh -executeConfigTools -responseFile Grid_home/install/  
response/product_timestamp.rsp
```

For Oracle Database:

```
$ ./runInstaller -executeConfigTools -responseFile $ORACLE_HOME/install/  
response/product_timestamp.rsp
```

For Oracle Database, you can also run the response file located in the directory `$ORACLE_HOME/install/response/`:

```
$ ./runInstaller -executeConfigTools -responseFile $ORACLE_HOME/install/  
response/db_install.rsp
```

The postinstallation configuration tool runs the installer in the graphical user interface mode, displaying the progress of the postinstallation configuration. Specify the `[-silent]` option to run the postinstallation configuration in the silent mode.

For example, for Oracle Grid Infrastructure:

```
$ ./gridSetup.sh -executeConfigTools -responseFile /u01/app/23.0.0/grid/  
install/response/grid_2022-01-09_01-03-36PM.rsp [-silent]
```

For Oracle Database:

```
$ ./runInstaller -executeConfigTools -responseFile /u01/app/oracle/product/  
23.0.0/dbhome_1/response/db_2022-01-09_01-03-36PM.rsp [-silent]
```

C

Completing Preinstallation Tasks Manually

You can complete the preinstallation configuration tasks manually.

Oracle recommends that you use Oracle Universal Installer and Configuration Verification Utility (CVU) fixup scripts to complete minimal configuration settings. If you cannot use fixup scripts, then complete minimum system settings manually.

- [Configuring SSH Manually on All Cluster Nodes](#)
SSH is used during installation to configure cluster member nodes, and SSH is used after installation by configuration assistants, Oracle Enterprise Manager, Opatch, and other features.
- [Configuring Storage Device Path Persistence Using Oracle ASMLIB](#)
To use Oracle ASMLIB to configure Oracle ASM devices, complete the following tasks:
- [Configuring Storage Device Path Persistence Manually](#)
You can maintain storage file path persistence by creating a rules file.
- [Configuring Kernel Parameters for Linux](#)
These topics explain how to configure kernel parameters manually for Linux if you cannot complete them using the fixup scripts.
- [Configuring Default Thread Limits Value for SUSE Linux](#)
If you are on SUSE Linux Enterprise Server 15 or later, then set the `DefaultTasksMax` parameter value to 65535.

Configuring SSH Manually on All Cluster Nodes

SSH is used during installation to configure cluster member nodes, and SSH is used after installation by configuration assistants, Oracle Enterprise Manager, Opatch, and other features.

- [About Passwordless SSH Configuration](#)
Passwordless SSH configuration is a mandatory installation requirement for Oracle Grid Infrastructure installation to configure cluster member nodes. You can use any method to establish passwordless SSH configuration.
- [Checking Existing SSH Configuration on the System](#)
Use this procedure to check if SSH is already configured and running on your server.
- [Configuring SSH on Cluster Nodes](#)
You must configure SSH separately for each Oracle software installation owner that you intend to use for installation.
- [Enabling SSH User Equivalency on Cluster Nodes](#)
After you have copied the `authorized_keys` file that contains all keys to each node in the cluster, complete the following procedure.

About Passwordless SSH Configuration

Passwordless SSH configuration is a mandatory installation requirement for Oracle Grid Infrastructure installation to configure cluster member nodes. You can use any method to establish passwordless SSH configuration.

Automatic Passwordless SSH configuration using OUI creates RSA encryption keys on all nodes of the cluster. If you have system restrictions that require you to set up SSH manually, such as using DSA keys, then use this procedure as a guide to set up passwordless SSH. If SSH is not available, then Oracle Universal Installer (OUI) attempts to use `rcp` instead. However, these services are disabled by default on most Linux systems.

To configure SSH, you are recommended to first create RSA or DSA keys on each cluster node, and then copy all the keys generated on all cluster node members into an authorized keys file that is identical on each node. Note that the SSH files must be readable only by `root` and by the software installation user (`oracle`, `grid`), as SSH ignores a private key file if it is accessible by others. In the examples that follow, the DSA key is used.



Note:

The supported version of SSH for Linux distributions is OpenSSH.

Checking Existing SSH Configuration on the System

Use this procedure to check if SSH is already configured and running on your server.

You need either an RSA or a DSA key for the SSH protocol. RSA is used with the SSH 1.5 protocol, while DSA is the default for the SSH 2.0 protocol. With OpenSSH, you can use either RSA or DSA. The instructions that follow are for SSH1. If you have an SSH2 installation, and you cannot use SSH1, then refer to your SSH distribution documentation to configure SSH1 compatibility or to configure SSH2 with DSA.

1. To determine if SSH is running, enter the following command:

```
$ pgrep sshd
```

If SSH is running, then the response to this command is one or more process ID numbers.

2. In the home directory of the installation software owner (`grid` or `oracle`), use the command `ls -al` to ensure that the `.ssh` directory is owned and writable only by the user.

Configuring SSH on Cluster Nodes

You must configure SSH separately for each Oracle software installation owner that you intend to use for installation.

- [Create SSH Directory and Create SSH Keys On Each Node](#)
To configure SSH, you must first create RSA or DSA keys on each cluster node.
- [Add All Keys to a Common `authorized_keys` File](#)
To configure SSH, copy all the generated keys on all cluster node members into an authorized keys file that is identical on each node.

Create SSH Directory and Create SSH Keys On Each Node

To configure SSH, you must first create RSA or DSA keys on each cluster node.

Complete the following steps on each node:

1. Log in as the software owner (in this example, the `grid` user).

- To ensure that you are logged in as the `grid` user, and to verify that the user ID matches the expected user ID you have assigned to the `grid` user, enter the commands:

```
$ id
$ id grid
```

Ensure that Oracle user group and user and the user terminal window process you are using have group and user IDs are identical.

For example:

```
uid=54322(grid) gid=54321(oinstall)
groups=54321(oinstall),54322(grid,asmadmin,asmdba)
$ id grid uid=54322(grid) gid=54321(oinstall)
groups=54321(oinstall),54322(grid,asmadmin,asmdba)
```

- If necessary, create the `.ssh` directory in the `grid` user's home directory, and set permissions on it to ensure that only the oracle user has read and write permissions:

```
$ mkdir ~/.ssh
$ chmod 700 ~/.ssh
```

Note that the SSH configuration fails if the permissions are not set to 700.

- Enter the following command:

```
$ /usr/bin/ssh-keygen -t dsa
```

Note:

If you have OpenSSH version 7.8 or higher installed on your system, then enter the following command to create SSH keys on each node:

```
$ /usr/bin/ssh-keygen -t dsa -m PEM
```

At the prompts, accept the default location for the key file (press **Enter**).

Never distribute the private key to anyone not authorized to perform Oracle software installations.

This command writes the DSA public key to the `~/.ssh/id_dsa.pub` file and the private key to the `~/.ssh/id_dsa` file.

- Repeat steps 1 through 4 on each node that you intend to make a member of the cluster, using the DSA key.

Add All Keys to a Common `authorized_keys` File

To configure SSH, copy all the generated keys on all cluster node members into an authorized keys file that is identical on each node.

Complete the following steps:

1. On the local node, change directories to the `.ssh` directory in the Oracle Grid Infrastructure owner's home directory (typically, either `grid` or `oracle`). Then, add the DSA key to the `authorized_keys` file using the following commands:

```
$ cat id_dsa.pub >> authorized_keys
$ ls
```

In the `.ssh` directory, you should see the `id_dsa.pub` keys that you have created, and the file `authorized_keys`.

2. On the local node, use SFTP (Secure FTP) to copy the `authorized_keys` file to the `oracle` user `.ssh` directory on a remote node. The following example is on a node called `node2`, with the Oracle Grid Infrastructure owner `grid`, where the `grid` user path is `/home/grid`:

```
[grid@node1 .ssh]$ sftp authorized_keys node2:/home/grid/.ssh/
```

- a. You are prompted to accept a DSA key. Enter `Yes`, and you see that the node you are copying to is added to the `known_hosts` file.
- b. When prompted, provide the password for the `grid` user, which should be the same on all nodes in the cluster. The `authorized_keys` file is copied to the remote node.

Your output should be similar to the following, where `xxx` represents parts of a valid IP address:

```
[grid@node1 .ssh]$ sftp authorized_keys node2:/home/grid/.ssh/
The authenticity of host 'node2 (xxx.xxx.173.152)' can't be established.
DSA key fingerprint is 7e:60:60:ae:40:40:d1:a6:f7:4e:zz:me:a7:48:ae:f6:7e.
Are you sure you want to continue connecting (yes/no)? yes
Warning: Permanently added 'node1,xxx.xxx.173.152' (dsa) to the list
of known hosts
grid@node2's password:
authorized_keys          100%          828           7.5MB/s       00:00
```

3. Using SSH, log in to the node where you copied the `authorized_keys` file. Then change to the `.ssh` directory, and using the `cat` command, add the DSA keys for the second node to the `authorized_keys` file, clicking **Enter** when you are prompted for a password, so that passwordless SSH is set up:

```
[grid@node1 .ssh]$ ssh node2 [grid@node2 grid]$ cd .ssh [grid@node2 ssh]
$ cat id_dsa.pub >> authorized_keys
```

4. Repeat steps 2 and 3 from each node to each other member node in the cluster.
5. When you have added keys from each cluster node member to the `authorized_keys` file on the last node you want to have as a cluster node member, then use `sftp` to copy the `authorized_keys` file with the keys from all nodes back to each cluster node member, overwriting the existing version on the other nodes. To confirm that you have all nodes in the `authorized_keys` file, enter the command `more authorized_keys`, and determine if there is a DSA key for each member node. The file lists the type of key (`ssh-dsa`), followed by the key, and then followed by the user and server. For example:

```
ssh-dsa AAAABBBB . . . = grid@node1
```

The `grid` user's `/.ssh/authorized_keys` file on every node must contain the contents from all of the `/.ssh/id_dsa.pub` files that you generated on all cluster nodes.

Enabling SSH User Equivalency on Cluster Nodes

After you have copied the `authorized_keys` file that contains all keys to each node in the cluster, complete the following procedure.

In this example, the Oracle Grid Infrastructure software owner is named `grid`.

Do the following:

1. On the system where you want to run OUI, log in as the `grid` user.
2. Use the following command syntax, where `hostname1`, `hostname2`, and so on (without domain name and in lowercase), are the public host names of nodes in the cluster to run SSH from the local node to each node, including from the local node to itself, and from each node to each other node:

```
[grid@nodename]$ ssh hostname1 date
[grid@nodename]$ ssh hostname2 date      .      .      .
```

At the end of this process, the public host name for each member node should be registered in the `known_hosts` file for all other cluster nodes. If you are using a remote client to connect to the local node, and you see a message similar to "Warning: No xauth data; using fake authentication data for X11 forwarding," then this means that your authorized keys file is configured correctly, but your SSH configuration has X11 forwarding enabled. To correct this issue, see [Setting Remote Display and X11 Forwarding Configuration](#).

3. Repeat step 2 on each cluster node member.

If you have configured SSH correctly, then you can now use the `ssh` or `sftp` commands without being prompted for a password. For example:

```
[grid@node1 ~]$ ssh node2 date
Mon Feb 26 23:34:42 UTC 2009
[grid@node1 ~]$ ssh node1 date
Mon Feb 26 23:34:48 UTC 2009
```

If any node prompts for a password, then verify that the `~/.ssh/authorized_keys` file on that node contains the correct public keys, and that you have created an Oracle software owner with identical group membership and IDs.

Configuring Storage Device Path Persistence Using Oracle ASMLIB

To use Oracle ASMLIB to configure Oracle ASM devices, complete the following tasks:

 **Note:**

To create a database during the installation using the Oracle ASM library driver, you must choose an installation method that runs ASMCA in interactive mode. You must also change the disk discovery string to `ORCL:*`.

Oracle ASMLIB is not supported on IBM:Linux on System z.

- [About Oracle ASM with Oracle ASMLIB](#)
Oracle ASMLIB maintains permissions and disk labels that are persistent on the storage device, so that the label is available even after an operating system upgrade.
- [Installing and Configuring Oracle ASMLIB Software](#)
Review this information to install and configure the Oracle Automatic Storage Management library driver software manually.
- [Configuring Disk Devices to Use Oracle ASMLIB](#)
Configure disk devices to use in an Oracle Automatic Storage Management disk group.
- [Administering Oracle ASMLIB and Disks](#)
Review this information to administer the Oracle Automatic Storage Management library driver and disks.
- [Configuring Oracle ASMLIB for Multipath Disks](#)
Additional configuration is required to use the Oracle Automatic Storage Management library Driver (ASMLIB) with third party vendor multipath disks.
- [Deinstalling Oracle ASMLIB On Oracle Grid Infrastructure](#)
If Oracle ASM library driver (Oracle ASMLIB) is installed but you do not use it for device path persistence, then deinstall Oracle ASMLIB.

About Oracle ASM with Oracle ASMLIB

Oracle ASMLIB maintains permissions and disk labels that are persistent on the storage device, so that the label is available even after an operating system upgrade.

The Oracle Automatic Storage Management library driver simplifies the configuration and management of block disk devices by eliminating the need to rebind block disk devices used with Oracle Automatic Storage Management (Oracle ASM) each time the system is restarted.

With Oracle ASMLIB, you define the range of disks you want to have made available as Oracle ASM disks. Oracle ASMLIB maintains permissions and disk labels that are persistent on the storage device, so that the label is available even after an operating system upgrade.

 **Note:**

- You must install Oracle ASMLib v3 (`oracleasm-lib-3.0.0` or later and `oracleasm-support-3.0.0` or later) on all Oracle Database servers with Oracle Linux 8 and later kernels.
- You must install Oracle ASMLib v2 (`oracleasm-lib-2.0.17` or later and `oracleasm-support-2.1.3` or later) on all Oracle Database servers with Oracle Linux 7 and earlier kernels.
- If you configure disks using Oracle ASMLIB, then you must change the disk discovery string to `ORCL:*`. If the diskstring is set to `ORCL:*`, or is left empty (""), then the installer discovers these disks.

Installing and Configuring Oracle ASMLIB Software

Review this information to install and configure the Oracle Automatic Storage Management library driver software manually.

Oracle ASMLIB is included with the Oracle Linux packages, and with SUSE Linux Enterprise Server. If you are a member of the Unbreakable Linux Network, then you can install the Oracle ASMLIB RPMs by subscribing to the Oracle Linux channel, and using `yum` to retrieve the most current package for your system and kernel. For additional information, see the following URL:

<http://www.oracle.com/technetwork/topics/linux/asmlib/index-101839.html>

 **Note:**

- You must install Oracle ASMLib v3 (`oracleasm-lib-3.0.0` or later and `oracleasm-support-3.0.0` or later) on all Oracle Database servers with Oracle Linux 8 and later kernels.
- You must install Oracle ASMLib v2 (`oracleasm-lib-2.0.17` or later and `oracleasm-support-2.1.3` or later) on all Oracle Database servers with Oracle Linux 7 and earlier kernels.
- You can also use `dnf` instead of `yum`. For more information, see [Comparing Yum Version with DNF](#)

1. Enter the following command to determine the kernel version and architecture of the system:

```
# uname -rm
```

2. Depending on your operating system version, download the required Oracle Automatic Storage Management library driver packages and driver:

<http://www.oracle.com/technetwork/server-storage/linux/asmlib/index-101839.html>

 **See Also:**

My Oracle Support note 1089399.1 for information about Oracle ASMLIB support with Red Hat distributions:

<https://support.oracle.com/rs?type=doc&id=1089399.1>

3. Switch to the `root` user:

```
$ su -
```

4. Depending on your operating system, you must install the `oracleasm-lib` and `oracleasm-support` packages for all Oracle ASMLIB installations.

 **Note:**

Oracle Unbreakable Enterprise Kernel includes driver module, so you do not need to install `kmod-oracleasm`.

Method 1 (recommended): If you have subscribed to Unbreakable Linux Network (ULN), then you can install the Oracle Automatic Storage Management library driver packages using a single `yum` command.

For Unbreakable Enterprise Kernel

```
# yum install oracleasm-support
# yum install oracleasm-lib
# yum install libbpf
# yum install libbpf-devel
```

For Red Hat Compatible Kernel

```
# yum install oracleasm-support
# yum install oracleasm-lib
```

Method 2: Alternatively, download the Oracle Automatic Storage Management library driver packages as described in Step 2 and run the following `rpm -ivh` commands to install the packages in sequence.

For Unbreakable Enterprise Kernel

```
# rpm -ivh oracleasm-support-version.arch.rpm
# rpm -ivh oracleasm-lib-version.arch.rpm
# rpm -ivh libbpf-version.arch.rpm
# rpm -ivh libbpf-devel-version.arch.rpm
```

For Red Hat Compatible Kernel

```
# rpm -ivh oracleasm-support-version.arch.rpm
# rpm -ivh oracleasm-lib-version.arch.rpm
```

Where *version* is the version of the Oracle Automatic Storage Management library driver, *arch* is the system architecture, and *kernel* is the version of the kernel that you are using.

For example, if you are using Oracle Linux 9 on an x86_64 system, then enter a command similar to the following:

```
# rpm -ivh oracleasm-lib-3.0.0-9.el9.x86_64 \
    oracleasm-support-3.0.0-21.el9.x86_64
```

- For SUSE Linux Enterprise Server 15, install the latest `oracleasm-lib` and `oracleasm-support` RPM from:

<https://www.oracle.com/linux/downloads/linux-asmlib-sles15-downloads.html>

 **Note:**

ASMLib v3 is not supported for SUSE Linux Enterprise Server.

Install the latest `oracleasm` driver module from the refreshed SUSE Linux Enterprise Server repository. The package name is `oracleasm-kmp-default`. For example, `oracleasm-kmp-default-2.0.8_k5.14.21_150500.55.36-150500.7.3.1.x86_64`

- Enter the following command to run the `oracleasm` initialization script with the `configure` option:

```
# /usr/sbin/oracleasm configure -i
```

 **Note:**

The `oracleasm` command in `/usr/sbin` is the command you should use. The `/etc/init.d` path is not deprecated, but the `oracleasm` binary in that path is now used typically for internal commands.

- Enter the following information in response to the prompts that the script displays:

Prompt	Suggested Response
Default user to own the driver interface:	<p>Standard groups and users configuration: Specify the Oracle software owner user (for example, <code>oracle</code>)</p> <p>Job role separation groups and users configuration: Specify the Grid Infrastructure software owner (for example, <code>grid</code>)</p>
Default group to own the driver interface:	<p>Standard groups and users configuration: Specify the OSDBA group for the database (for example, <code>dba</code>).</p> <p>Job role separation groups and users configuration: Specify the OSASM group for storage administration (for example, <code>asmadmin</code>).</p>
Start Oracle ASM Library driver on boot (y/n):	Enter <code>y</code> to start the Oracle Automatic Storage Management library driver when the system starts.

Prompt	Suggested Response
Scan for Oracle ASM disks on boot (y/n)	Enter <code>y</code> to scan for Oracle ASM disks when the system starts.

The script completes the following tasks:

- Creates the `/etc/sysconfig/oracleasm` configuration file
- Mounts the ASMLIB driver file system

 **Note:**

The Oracle ASMLIB file system is not a regular file system. It is used only by the Oracle ASM library to communicate with the Oracle ASMLIB.

8. Enter the following command to enable the Oracle ASMLIB file system:

```
# systemctl enable oracleasm
```

9. Enter the following command to start the Oracle ASMLIB file system:

```
# systemctl start oracleasm
```

Configuring Disk Devices to Use Oracle ASMLIB

Configure disk devices to use in an Oracle Automatic Storage Management disk group.

1. If you intend to use IDE, SCSI, or RAID devices in the Oracle Automatic Storage Management disk group, then perform the following steps:
 - a. Install or configure the disk devices that you intend to use for the disk group and restart the system.
 - b. Enter the following command to identify the device name for the disks to use:

```
# /sbin/fdisk -l
```

Depending on the type of disk, the device name can vary.

Table C-1 Device Name Formats Based on Disk Type

Disk Type	Device Name Format	Description
IDE disk	<code>/dev/hdxn</code>	In this example, <i>x</i> is a letter that identifies the IDE disk, and <i>n</i> is the partition number. For example, <code>/dev/hda</code> is the first disk on the first IDE bus.
SCSI disk	<code>/dev/sdxn</code>	In this example, <i>x</i> is a letter that identifies the IDE disk, and <i>n</i> is the partition number. For example, <code>/dev/hda</code> is the first disk on the first IDE bus.

Table C-1 (Cont.) Device Name Formats Based on Disk Type

Disk Type	Device Name Format	Description
RAID disk	/dev/rd/cxdypz /dev/ida/cxdypz	Depending on the RAID controller, RAID devices can have different device names. In the examples shown, <i>x</i> is a number that identifies the controller, <i>y</i> is a number that identifies the disk, and <i>z</i> is a number that identifies the partition. For example, /dev/ida/c0d1 is the second logical drive on the first controller.

To include devices in a disk group, you can specify either whole-drive device names or partition device names.

 **Note:**

Oracle recommends that you create a single whole-disk partition on each disk to use.

- c. Use either `fdisk` or `parted` to create a single whole-disk partition on the disk devices.
2. Enter a command similar to the following to mark a disk as an Oracle Automatic Storage Management disk:

```
# /usr/sbin/oracleasm createdisk DISK1 /dev/sdb1
```

In this example, `DISK1` is a name assigned to the disk.

 **Note:**

- The disk names you specify can contain uppercase letters, numbers, and the underscore character. They must start with an uppercase letter.
- To create a database during the installation using the Oracle Automatic Storage Management library driver, you must change the disk discovery string to `ORCL:*`.
- If you are using a multi-pathing disk driver with Oracle ASM, then make sure that you specify the correct logical device name for the disk.

3. To make the disk available on the other nodes in the cluster, enter the following command as `root` on each node:

```
# /usr/sbin/oracleasm scandisks
```

This command identifies shared disks attached to the node that are marked as Oracle ASM disks.

Administering Oracle ASMLIB and Disks

Review this information to administer the Oracle Automatic Storage Management library driver and disks.

Oracle ASMLib Administration

To administer the Oracle Automatic Storage Management library driver and disks, use the `/usr/sbin/oracleasm` initialization script with different options, as described in the following table:

Table C-2 Disk Management Tasks Using ORACLEASM

Task	Command Example	Description
Configure or reconfigure ASMLIB	<code>oracleasm configure -i</code>	Use the <code>configure</code> option to reconfigure the Oracle Automatic Storage Management library driver, if necessary. To see command options, enter <code>oracleasm configure</code> without the <code>-i</code> flag.
Change system restart load options for ASMLIB	<code>oracleasm configure -e</code>	Options are <code>-e</code> to enable and <code>-d</code> to disable. Use the <code>-e</code> and <code>-d</code> options to change the actions of the Oracle Automatic Storage Management library driver when the system starts. The <code>-e</code> option causes the Oracle Automatic Storage Management library driver to load when the system starts.
Load or unload ASMLIB without restarting the system	<code>oracleasm init</code>	Options are <code>init</code> to load and <code>exit</code> to unload. Use the <code>init</code> and <code>exit</code> options to load or unload the Oracle Automatic Storage Management library driver without restarting the system.
Mark a disk for use with ASMLIB	<code>oracleasm createdisk VOL1 /dev/sda1</code>	Use the <code>createdisk</code> option to mark a disk device for use with the Oracle Automatic Storage Management library driver and give it a name, where <i>labelname</i> is the name you want to use to mark the device, and <i>devicepath</i> is the path to the device: <code>oracleasm createdisk labelname devicepath</code>
Unmark a named disk device	<code>oracleasm deletedisk VOL1</code>	Use the <code>deletedisk</code> option to unmark a named disk device, where <i>diskname</i> is the name of the disk: <code>oracleasm deletedisk diskname</code> Caution: Do not use this command to unmark disks that are being used by an Oracle Automatic Storage Management disk group. You must delete the disk from the Oracle Automatic Storage Management disk group before you unmark it.
Determine if ASMLIB is using a disk device	<code>oracleasm querydisk</code>	Use the <code>querydisk</code> option to determine if a disk device or disk name is being used by the Oracle Automatic Storage Management library driver, where <i>diskname_devicename</i> is the name of the disk or device that you want to query: <code>oracleasm querydisk diskname_devicename</code>
List Oracle ASMLIB disks	<code>oracleasm listdisks</code>	Use the <code>listdisks</code> option to list the disk names of marked Oracle ASM library driver disks.

Table C-2 (Cont.) Disk Management Tasks Using ORACLEASM

Task	Command Example	Description
Identify disks marked as ASMLIB disks	<code>oracleasm scandisks</code>	Use the <code>scandisks</code> option to enable cluster nodes to identify which shared disks have been marked as ASMLIB disks on another node.
Rename ASMLIB disks	<code>oracleasm renamedisk VOL1 VOL2</code>	<p>Use the <code>renamedisk</code> option to change the label of an Oracle ASM library driver disk or device by using the following syntax, where <i>manager</i> specifies the manager device, <i>label_device</i> specifies the disk you intend to rename, as specified either by OracleASM label name or by the device path, and <i>new_label</i> specifies the new label you want to use for the disk:</p> <pre>oracleasm renamedisk [-l manager] [-v] label_device new_label</pre> <p>Use the <code>-v</code> flag to provide a verbose output for debugging.</p> <p>Caution: You must ensure that all Oracle Database and Oracle ASM instances have ceased using the disk before you relabel the disk. If you do not do this, then you may lose data.</p>

Configuring Oracle ASMLIB for Multipath Disks

Additional configuration is required to use the Oracle Automatic Storage Management library Driver (ASMLIB) with third party vendor multipath disks.

- [About Using Oracle ASM with Multipath Disks](#)
Oracle ASM requires that each disk is uniquely identified. If the same disk appears under multiple paths, then it causes errors.
- [About Disk Scan Ordering](#)
The `ORACLEASM_SCANORDER` variable specifies disks to be scanned first.
- [Configuring Disk Scan Ordering to Select Multipath Disks](#)
To configure ASMLIB to select multipath disks first, complete the following procedure.
- [Configuring Disk Order Scan to Exclude Single Path Disks](#)
To configure ASMLIB to exclude particular single path disks, complete the following procedure.



See Also:

My Oracle Support site for updates to supported storage options:
<https://support.oracle.com/>

About Using Oracle ASM with Multipath Disks

Oracle ASM requires that each disk is uniquely identified. If the same disk appears under multiple paths, then it causes errors.

In a multipath disk configuration, the same disk can appear three times: the initial path to the disk, the second path to the disk, and the multipath disk access point.

For example: If you have one local disk, `/dev/sda`, and one disk attached with external storage, then your server shows two connections, or paths, to that external storage. The Linux SCSI driver shows both paths. They appear as `/dev/sdb` and `/dev/sdc`. The system may access either `/dev/sdb` or `/dev/sdc`, but the access is to the same disk.

If you enable multipathing, then you have a multipath disk (for example, `/dev/multipatha`), which can access both `/dev/sdb` and `/dev/sdc`; any I/O to `multipatha` can use either the `sdb` or `sdc` path. If a system is using the `/dev/sdb` path, and that cable is unplugged, then the system shows an error. But the multipath disk will switch from the `/dev/sdb` path to the `/dev/sdc` path.

Most system software is unaware of multipath configurations. They can use any paths (`sdb`, `sdc` or `multipatha`). ASMLIB also is unaware of multipath configurations.

By default, ASMLIB recognizes the first disk path that Linux reports to it, but because it imprints an identity on that disk, it recognizes that disk only under one path. Depending on your storage driver, it may recognize the multipath disk, or it may recognize one of the single disk paths.

Instead of relying on the default, you should configure Oracle ASM to recognize the multipath disk.

About Disk Scan Ordering

The `ORACLEASM_SCANORDER` variable specifies disks to be scanned first.

The ASMLIB configuration file is located in the path `/etc/sysconfig/oracleasm`. It contains all the startup configuration you specified with the command `/usr/sbin/oracleasm configure`. That command cannot configure scan ordering.

The configuration file contains many configuration variables. The `ORACLEASM_SCANEXCLUDE` variable specifies the disks that are to be ignored.

Configure values for `ORACLEASM_SCANORDER` using space-delimited prefix strings. A *prefix string* is the common string associated with a type of disk. For example, if you use the prefix string `sd`, then this string matches all SCSI devices, including `/dev/sda`, `/dev/sdb`, `/dev/sdc` and so on. Note that these are not globs. They do not use wild cards. They are simple prefixes. Also note that the path is not a part of the prefix. For example, the `/dev/` path is not part of the prefix for SCSI disks that are in the path `/dev/sd*`.

For Oracle Linux and Red Hat Enterprise Linux, when scanning, the kernel sees the devices as `/dev/mapper/XXX` entries. By default, the device file naming scheme `udev` creates the `/dev/mapper/XXX` names for human readability. Any configuration using `ORACLEASM_SCANORDER` should use the `/dev/mapper/XXX` entries.

Configuring Disk Scan Ordering to Select Multipath Disks

To configure ASMLIB to select multipath disks first, complete the following procedure.

1. Using a text editor, open the ASMLIB configuration file `/etc/sysconfig/oracleasm`.
2. Edit the `ORACLEASM_SCANORDER` variable to provide the prefix path of the multipath disks.

For example, if the multipath disks use the prefix `multipath` (`/dev/mapper/multipatha`, `/dev/mapper/multipathb` and so on), and the multipath disks mount SCSI disks, then provide a prefix path similar to the following:

```
ORACLEASM_SCANORDER="multipath sd"
```

3. Save the file.

When you have completed this procedure, then when ASMLIB scans disks, it first scans all disks with the prefix string `multipath`, and labels these disks as Oracle ASM disks using the `/dev/mapper/multipathX` value. It then scans all disks with the prefix string `sd`. However, because ASMLIB recognizes that these disks have already been labeled with the `/dev/mapper/multipath` string values, it ignores these disks. After scanning for the prefix strings `multipath` and `sd`, Oracle ASM then scans for any other disks that do not match the scan order.

In the example in step 2, the key word `multipath` is actually the alias for multipath devices configured in `/etc/multipath.conf` under the `multipaths` section. The default device name is in the format `/dev/mapper/mpath*` (or a similar path). For example:

```
multipaths {
    multipath {
        wwid                3600508b4000156d700012000000b0000
        alias                multipath
        ...
    }
    multipath {
        ...
        alias                mympath
        ...
    }
    ...
}
```

Configuring Disk Order Scan to Exclude Single Path Disks

To configure ASMLIB to exclude particular single path disks, complete the following procedure.

1. Using a text editor, open the ASMLIB configuration file `/etc/sysconfig/oracleasm`.
2. Edit the `ORACLEASM_SCANEXCLUDE` variable to provide the prefix path of the single path disks.

For example, if you want to exclude the single path disks `/dev/sdb` and `/dev/sdc`, then provide a prefix path similar to the following:

```
ORACLEASM_SCANEXCLUDE="sdb sdc"
```

3. Save the file.

When you have completed this procedure, then when ASMLIB scans disks, it scans all disks except for the disks with the `sdb` and `sdc` prefixes, so that it ignores `/dev/sdb` and `/dev/sdc`. It does not ignore other SCSI disks, nor multipath disks. If you have a multipath disk (for example, `/dev/multipatha`), which accesses both `/dev/sdb` and `/dev/sdc`, but you have configured ASMLIB to ignore `sdb` and `sdc`, then ASMLIB ignores these disks and instead marks only the multipath disk as an Oracle ASM disk.

Deinstalling Oracle ASMLIB On Oracle Grid Infrastructure

If Oracle ASM library driver (Oracle ASMLIB) is installed but you do not use it for device path persistence, then deinstall Oracle ASMLIB.

1. Log in as `root`.
2. Stop Oracle ASM and any running database instance on the node:

```
# srvctl stop instance -d db_unique_name-node node_name
# srvctl stop asm -node node_name
```

To stop the last Oracle Flex ASM instance on the node, stop the Oracle Clusterware stack:

```
# Grid_home/bin/crsctl stop crs
```

3. Unload ASMLIB without restarting the system:

```
# /usr/sbin/oracleasm exit
```

4. Stop Oracle ASMLIB:

```
# /usr/sbin/oracleasm configure -d
```

5. Remove the `oracleasm` library and tools RPMs:

```
# rpm -e oracleasm-support
```

```
# rpm -e oracleasmlib
```

6. Check if any `oracleasm` RPMs are remaining:

```
# rpm -qa | grep oracleasm
```

7. If any `oracleasm` configuration files are remaining, remove them:

```
# rpm -qa | grep oracleasm | xargs rpm -e
```

Oracle ASMLIB and associated RPMs are now removed.

Start the Oracle Clusterware stack. Optionally, you can install and configure Oracle ASM Filter Driver (Oracle ASMTFD) before starting the Oracle Clusterware stack.

Oracle Automatic Storage Management Administrator's Guide

Configuring Storage Device Path Persistence Manually

You can maintain storage file path persistence by creating a rules file.

- [About Device Path Persistence](#)
Understand device path persistence for Oracle Automatic Storage Management (Oracle ASM).

- [Configuring Device Persistence Manually for Oracle ASM](#)
Complete these tasks to create device path persistence manually for Oracle ASM.

About Device Path Persistence

Understand device path persistence for Oracle Automatic Storage Management (Oracle ASM).

By default, the device file naming scheme `udev` dynamically creates device file names when the server is started, and assigns ownership of them to `root`. If `udev` applies default settings, then it changes Oracle device file names and owners for the disks, making the disks inaccessible when the server is restarted. For example, a voting disk on a device named `/dev/sdd` owned by the user `grid` may be on a device named `/dev/sdf` owned by `root` after restarting the server.

If you use Oracle ASMFD, then you do not have to ensure permissions and device path persistence in `udev`.

If you do not use Oracle ASMFD, then you must create a custom rules file. Linux vendors customize their `udev` configurations and use different orders for reading rules files. For example, on some Linux distributions when `udev` is started, it sequentially carries out rules (configuration directives) defined in rules files. These files are in the path `/etc/udev/rules.d/`. Rules files are read in lexical order. For example, rules in the file `10-wacom.rules` are parsed and carried out before rules in the rules file `90-ib.rules`.

When specifying the device information in the `udev` rules file, ensure that the `OWNER`, `GROUP`, and `MODE` are specified before all other characteristics in the order shown. For example, to include the characteristic `ACTION` on the `UDEV` line, specify `ACTION` after `OWNER`, `GROUP`, and `MODE`.

Where rules files describe the same devices, on the supported Linux kernel versions, the last file read is the one that is applied.

Configuring Device Persistence Manually for Oracle ASM

Complete these tasks to create device path persistence manually for Oracle ASM.

1. On existing systems (single instance or clustered), to obtain current mount paths, run the command `scsi_id (/sbin/scsi_id)` on storage devices on a server to obtain their unique device identifiers. When you run the command `scsi_id` with the `-s` argument, the device path and name you provide should be relative to the `sysfs` directory `/sys` (for example, `/block/device`) when referring to `/sys/block/device`.

For example, as the `root` user:

```
# /sbin/scsi_id -g -s /block/sdb/sdb1
360a98000686f6959684a453333524174

# /sbin/scsi_id -g -s /block/sde/sde1
360a98000686f6959684a453333524179
```

Record the unique SCSI identifiers, so you can provide them when required.

 **Note:**

The command `scsi_id` should return the same device identifier value for a given device, regardless of which node the command is run from.

2. Configure SCSI devices as trusted devices, by editing the `/etc/scsi_id.config` file and adding `options=-g` to the file.

```
# cat > /etc/scsi_id.config
vendor="ATA",options=-p 0x80
options=-g
```

3. Using a text editor, create a UDEV rules file for the Oracle ASM devices, setting permissions to 0660 for the installation owner and the operating system group you have designated the OSDBA for Oracle ASM group, whose members are granted access privileges to Oracle ASM. For example, on Oracle Linux, to create a role-based configuration `rules.d` file where the installation owner is `grid` and the OSDBA group for Oracle ASM is `asmdba`, enter commands similar to the following:

```
# vi /etc/udev/rules.d/99-oracle-asmdevices.rules

KERNEL=="sdb1, OWNER="grid", GROUP="asmdba", MODE="0660",
BUS=="scsi", PROGRAM=="/sbin/scsi_id", RESULT=="14f70656e66696c00000000"
KERNEL=="sdc1", OWNER="grid", GROUP="asmdba", MODE="0660",
BUS=="scsi", PROGRAM=="/sbin/scsi_id", RESULT=="14f70656e66696c00000001"
KERNEL=="sdd1", OWNER="grid", GROUP="asmdba", MODE="0660",
BUS=="scsi", PROGRAM=="/sbin/scsi_id", RESULT=="14f70656e66696c00000002"
```

4. On clustered systems, copy the `rules.d` file to all other nodes on the cluster. For example:

```
# sftp 99-oracle-asmdevices.rules root@node2:/etc/udev/rules.d/99-oracle-
asmdevices.rules
```

5. Run the `partprobe` command using the syntax `/sbin/partprobe devicename`.

For example:

```
# /sbin/partprobe /dev/sdc1
# /sbin/partprobe /dev/sdd1
# /sbin/partprobe /dev/sde1
# /sbin/partprobe /dev/sdf1
```

6. Run the command `udevtest (/sbin/udevtest)` to test the UDEV rules configuration you have created. The output should indicate that the devices are available and the rules are applied as expected. For example, for `/dev/ssd1`:

```
# udevtest /block/sdd/sdd1
main: looking at device '/block/sdd/sdd1' from subsystem 'block'
udev_rules_get_name: add symlink
'disk/by-id/scsi-360a98000686f6959684a453333524174-part1'
udev_rules_get_name: add symlink
'disk/by-path/ip-192.168.1.1:3260-iscsi-iqn.1992-08.com.netapp:sn.887085-
part1'
udev_node_mknod: preserve file '/dev/.tmp-8-17', because it has correct
```



```

dev_t
run_program: '/lib/udev/vol_id --export /dev/.tmp-8-17'
run_program: '/lib/udev/vol_id' returned with status 4
run_program: '/sbin/scsi_id'
run_program: '/sbin/scsi_id' (stdout) '360a98000686f6959684a453333524174'
run_program: '/sbin/scsi_id' returned with status 0
udev_rules_get_name: rule applied, 'sdd1' becomes 'data1'
udev_device_event: device '/block/sdd/sdd1' validate currently present
symlinks
udev_node_add: creating device node '/dev/data1', major = '8', minor =
'17',
mode = '0640', uid = '0', gid = '500'
udev_node_add: creating symlink
'/dev/disk/by-id/scsi-360a98000686f6959684a453333524174-part1' to '../..//
data1'
udev_node_add: creating symlink
'/dev/disk/by-path/ip-192.168.1.1:3260-iscsi-
iqn.1992-08.com.netapp:sn.84187085
-part1' to '../..//data1'
main: run: 'socket:/org/kernel/udev/monitor'
main: run: '/lib/udev/udev_run_devd'
main: run: 'socket:/org/freedesktop/hal/udev_event'
main: run: '/sbin/pam_console_apply /dev/data1
/dev/disk/by-id/scsi-360a98000686f6959684a453333524174-part1
/dev/disk/by-path/ip-192.168.1.1:3260-iscsi-
iqn.1992-08.com.netapp:sn.84187085-
part1'

```

In the example output, note that applying the rules renames OCR device `/dev/sdd1` to `/dev/data1`.

7. Load the rules and restart the UDEV service. For example:

- Oracle Linux and Red Hat Enterprise Linux

```
# udevadm control --reload-rules && udevadm trigger
```

- SUSE Linux Enterprise Server

```
# /etc/init.d boot.udev restart
```

Verify that the device permissions and ownerships are set correctly.

Configuring Kernel Parameters for Linux

These topics explain how to configure kernel parameters manually for Linux if you cannot complete them using the fixup scripts.

- [Minimum Parameter Settings for Installation](#)
Use this table to set parameters manually if you cannot use the fixup scripts.
- [Changing Kernel Parameter Values](#)
Use these instructions to display and change the kernel parameter values if they are different from the minimum recommended value.

- [Configuring Additional Kernel Settings for SUSE Linux](#)
Additional kernel parameter settings configuration is required on SUSE Linux Enterprise Server systems.
- [Setting UDP and TCP Kernel Parameters Manually](#)
If you do not use a Fixup script or CVU to set ephemeral ports, then follow these guidelines to ensure smooth and high performance experience with least errors or issues.

Minimum Parameter Settings for Installation

Use this table to set parameters manually if you cannot use the fixup scripts.

 **Note:**

- Unless otherwise specified, the kernel parameter and shell limit values shown in the following table are minimum values only. For production database systems, Oracle recommends that you tune these values to optimize the performance of the system. See the operating system documentation for more information about tuning kernel parameters.
- If the current value for any parameter is greater than the value listed in this table, then the Fixup scripts do not change the value of that parameter.

Table C-3 Minimum Operating System Resource Parameter Settings

Parameter	Value	File
semmsl	250	/proc/sys/kernel/sem
semmns	32000	
semopm	100	
semmni	128	
shmall	Greater than or equal to the value of shmmax, in pages.	/proc/sys/kernel/shmall
shmmax	Half the size of physical memory in bytes See My Oracle Support Note 567506.1 for additional information about configuring shmmax.	/proc/sys/kernel/shmmax
shmmni	4096	/proc/sys/kernel/shmmni
panic_on_oops	1	/proc/sys/kernel/panic_on_oops
kernel.panic	10 (seconds)	/proc/sys/kernel/panic
file-max	6815744	/proc/sys/fs/file-max
aio-max-nr	1048576 Note: This value limits concurrent outstanding requests and should be set to avoid I/O subsystem failures.	/proc/sys/fs/aio-max-nr

Table C-3 (Cont.) Minimum Operating System Resource Parameter Settings

Parameter	Value	File
ip_local_port_range	Minimum: 9000 Maximum: 65535	/proc/sys/net/ipv4/ ip_local_port_range
rmem_default	262144	/proc/sys/net/core/ rmem_default
rmem_max	4194304	/proc/sys/net/core/ rmem_max
wmem_default	262144	/proc/sys/net/core/ wmem_default
wmem_max	1048576	/proc/sys/net/core/ wmem_max

Changing Kernel Parameter Values

Use these instructions to display and change the kernel parameter values if they are different from the minimum recommended value.

Use the following commands to display the current values of the kernel parameters:

Table C-4 Commands to Display Kernel Parameter Values

Parameter	Command
semmsl, semmns, semopm, and semmni	# /sbin/sysctl -a grep sem This command displays the value of the semaphore parameters in the order listed.
shmall, shmmax, and shmmni	# /sbin/sysctl -a grep shm This command displays the details of the shared memory segment sizes.
file-max	# /sbin/sysctl -a grep file-max This command displays the maximum number of file handles.
ip_local_port_range	# /sbin/sysctl -a grep ip_local_port_range This command displays a range of port numbers.
rmem_default	# /sbin/sysctl -a grep rmem_default
rmem_max	# /sbin/sysctl -a grep rmem_max
wmem_default	# /sbin/sysctl -a grep wmem_default
wmem_max	# /sbin/sysctl -a grep wmem_max
aio-max-nr	# /sbin/sysctl -a grep aio-max-nr

If you used the Oracle Database Preinstallation RPM to complete you preinstallation configuration tasks, then the Oracle Database Preinstallation RPM sets these kernel parameters for you. However, if you did not use the Oracle Database Preinstallation RPM or the kernel parameters are different from the minimum recommended value, then to change these kernel parameter values:

1. Using any text editor, create or edit the `/etc/sysctl.d/97-oracle-database-sysctl.conf` file, and add or edit lines similar to:

```
fs.aio-max-nr = 1048576
fs.file-max = 6815744
kernel.shmall = 2097152
kernel.shmmax = 4294967295
kernel.shmmni = 4096
kernel.sem = 250 32000 100 128
net.ipv4.ip_local_port_range = 9000 65535
net.core.rmem_default = 262144
net.core.rmem_max = 4194304
net.core.wmem_default = 262144
net.core.wmem_max = 1048576
```

By specifying the values in the `/etc/sysctl.d/97-oracle-database-sysctl.conf` file, the values persist on system restarts.

2. To change the current values of the kernel parameters:

```
# /sbin/sysctl --system
```

Review the output. If the values are incorrect, edit the `/etc/sysctl.d/97-oracle-database-sysctl.conf` file, then enter this command again.

3. Confirm that the values are set correctly:

```
# /sbin/sysctl -a
```

4. Restart the computer, or run `sysctl --system` to make the changes in the `/etc/sysctl.d/97-oracle-database-sysctl.conf` file available in the active kernel memory.

Guidelines for Setting Kernel Parameter Values

- If you used the Oracle Database Preinstallation RPM, then your kernel parameter settings reside in the `/etc/sysctl.d/99-oracle-database-server-23ai-preinstall-sysctl.conf` file.
- Include lines only for the kernel parameter values to change. For the semaphore parameters (`kernel.sem`), you must specify all four values. If any of the current values are larger than the minimum value, then specify the larger value.
- The `/etc/sysctl.conf` file has been deprecated.
- To obtain optimal performance and functionality from the Linux Kernel for `ip_local_port_range`, ensure that the selected range is large enough to accommodate the workload. Also ensure that the polarity is reversed for minimum and maximum values, that is, one value is even and the other is odd.
- Avoid setting kernel parameter values in multiple files under `/etc/sysctl.d/`. The file with a lexicographically later name under `/etc/sysctl.d/` takes precedence, followed by `/etc/sysctl.conf`. Oracle recommends that you use the Oracle Database Preinstallation RPM which, among other preinstallation tasks, also sets the kernel parameter values for your database installation.

 **See Also:**

`sysctl.conf(5)` and `sysctl.d(5)` man pages for more information

Configuring Additional Kernel Settings for SUSE Linux

Additional kernel parameter settings configuration is required on SUSE Linux Enterprise Server systems.

Perform these steps on SUSE Linux Enterprise Server systems only:

1. Enter the following command to enable the system to read the `/etc/sysctl.conf` file when it restarts:

```
# /sbin/chkconfig boot.sysctl on
```

2. Enter the GID of the `oinstall` group as the value for the parameter `/proc/sys/vm/hugetlb_shm_group`.

For example, where the `oinstall` group GID is 501:

```
# echo 501 > /proc/sys/vm/hugetlb_shm_group
```

Use `vi` to add the following text to `/etc/sysctl.conf`, and enable the `boot.sysctl` script to run on system restart:

```
vm.hugetlb_shm_group=501
```

 **Note:**

Only one group can be defined as the `vm.hugetlb_shm_group`.

Setting UDP and TCP Kernel Parameters Manually

If you do not use a Fixup script or CVU to set ephemeral ports, then follow these guidelines to ensure smooth and high performance experience with least errors or issues.

- Choose lower and higher numbers that are even/odd not both odd or both even.
- Ensure that the lower range is set to 9000 or higher to avoid *well known ports* and those commonly registered for use by Oracle and other vendors or servers.
- Set the port range high enough to include reserved ports for any applications you may intend to use and large enough ephemeral ports for the anticipated server workload.

For example, with IPv4, use the following command to check your current range for ephemeral ports:

```
$ cat /proc/sys/net/ipv4/ip_local_port_range  
32768 61001
```

In the preceding example, the lowest port (32768) and the highest port (61000) are set to the default range.

If necessary, update the UDP and TCP ephemeral port range to a range high enough for anticipated system workloads, and to ensure that the ephemeral port range starts at 9000 and above. For example:

```
# echo 9000 65535 > /proc/sys/net/ipv4/ip_local_port_range
```

Oracle recommends that you make these settings permanent. For example, as `root`, use a text editor to open `/etc/sysctl.conf`, and add or change to the following:

`net.ipv4.ip_local_port_range = 9000 65535`, and then restart the network:

```
$ sudo systemctl restart NetworkManager.service
```

Refer to your Linux distribution system administration documentation for information about automating ephemeral port range alteration on system restarts.

Configuring Default Thread Limits Value for SUSE Linux

If you are on SUSE Linux Enterprise Server 15 or later, then set the `DefaultTasksMax` parameter value to 65535.

Increase the default thread limits, `DefaultTasksMax` value from 512 to 65535 to avoid running into service failures.

1. View the contents of `/etc/systemd/system.conf` to know the current `DefaultTasksMax` value. Alternatively, run the following command:

```
$ systemctl show --property DefaultTasksMax
```

2. If your `DefaultTasksMax` value is not 65535, then uncomment the line in `/etc/systemd/system.conf` and set the value to 65535.
3. To enable the new settings, reboot your system or run the following command:

```
$ systemctl daemon-reload
```

D

Optimal Flexible Architecture

Oracle Optimal Flexible Architecture (OFA) rules are a set of configuration guidelines created to ensure well-organized Oracle installations, which simplifies administration, support and maintenance.

- [About the Optimal Flexible Architecture Standard](#)
Oracle Optimal Flexible Architecture (OFA) rules help you to organize database software and configure databases to allow multiple databases, of different versions, owned by different users to coexist.
- [About Multiple Oracle Homes Support](#)
Oracle Database supports multiple Oracle homes. You can install this release or earlier releases of the software more than once on the same system, in different Oracle home directories.
- [About the Oracle Inventory Directory and Installation](#)
The directory that you designate as the Oracle Inventory directory (oraInventory) stores an inventory of all software installed on the system.
- [Oracle Base Directory Naming Convention](#)
The Oracle Base directory is the database home directory for Oracle Database installation owners, and the log file location for Oracle Grid Infrastructure owners.
- [Oracle Home Directory Naming Convention](#)
By default, Oracle Universal Installer configures Oracle home directories using these Oracle Optimal Flexible Architecture conventions.
- [Optimal Flexible Architecture File Path Examples](#)
Review examples of hierarchical file mappings of an Optimal Flexible Architecture-compliant installation.

About the Optimal Flexible Architecture Standard

Oracle Optimal Flexible Architecture (OFA) rules help you to organize database software and configure databases to allow multiple databases, of different versions, owned by different users to coexist.

In earlier Oracle Database releases, the OFA rules provided optimal system performance by isolating fragmentation and minimizing contention. In current releases, OFA rules provide consistency in database management and support, and simplifies expanding or adding databases, or adding additional hardware.

By default, Oracle Universal Installer places Oracle Database components in directory locations and with permissions in compliance with OFA rules. Oracle recommends that you configure all Oracle components in accordance with OFA guidelines.

Oracle recommends that you accept the OFA default. Following OFA rules is especially of value if the database is large, or if you plan to have multiple databases.

**Note:**

OFA assists in identification of an ORACLE_BASE with its Automatic Diagnostic Repository (ADR) diagnostic data to properly collect incidents.

About Multiple Oracle Homes Support

Oracle Database supports multiple Oracle homes. You can install this release or earlier releases of the software more than once on the same system, in different Oracle home directories.

Careful selection of mount point names can make Oracle software easier to administer. Configuring multiple Oracle homes in compliance with Optimal Flexible Architecture (OFA) rules provides the following advantages:

- You can install this release, or earlier releases of the software, more than once on the same system, in different Oracle home directories. However, you cannot install products from one release of Oracle Database into an Oracle home directory of a different release.
- Multiple databases, of different versions, owned by different users can coexist concurrently.
- To install Oracle Database software in multiple Oracle homes, you must extract the image file in each Oracle home, and then run the setup wizard from the respective Oracle home.
- You must install a new Oracle Database release in a new Oracle home that is separate from earlier releases of Oracle Database.

You cannot install multiple releases in one Oracle home. Oracle recommends that you create a separate Oracle Database Oracle home for each release, in accordance with the Optimal Flexible Architecture (OFA) guidelines.

- In production, the Oracle Database server software release is the release number in the format of major and RU release number. For example, with the release number 19.7.0.0.0, the major release is 19 and the RU release number is 7.
- Later Oracle Database releases can access earlier Oracle Database releases. However, this access is only for upgrades. For example, Oracle Database 23ai can access an Oracle Database 19c if the 19c database is started up in upgrade mode.
- Structured organization of directories and files, and consistent naming for database files simplify database administration.
- Login home directories are not at risk when database administrators add, move, or delete Oracle home directories.
- For information about release support timelines, refer to My Oracle Support Doc ID 742060.1

Related Topics

- [My Oracle Support Note 742060.1](#)

About the Oracle Inventory Directory and Installation

The directory that you designate as the Oracle Inventory directory (oraInventory) stores an inventory of all software installed on the system.

All Oracle software installation owners on a server are granted the OINSTALL privileges to read and write to this directory. If you have previous Oracle software installations on a server,

then additional Oracle software installations detect this directory from the `/etc/oraInst.loc` file, and continue to use that Oracle Inventory. Ensure that the group designated as the OINSTALL group is available as a primary group for all planned Oracle software installation owners.

If you are installing Oracle software for the first time, then OUI creates an Oracle base and central inventory, and creates an Oracle inventory using information in the following priority:

- In the path indicated in the `ORACLE_BASE` environment variable set for the installation owner user account
- In an Optimal Flexible Architecture (OFA) path (`u[01–99]/app/owner` where *owner* is the name of the user account running the installation), and that user account has permissions to write to that path
- In the user home directory, in the path `/app/owner`, where *owner* is the name of the user account running the installation

For example:

If you are performing an Oracle Database installation, and you set `ORACLE_BASE` for user `oracle` to the path `/u01/app/oracle` before installation, and grant 755 permissions to `oracle` for that path, then Oracle Universal Installer creates the Oracle Inventory directory one level above the `ORACLE_BASE` in the path `ORACLE_BASE/./oraInventory`, so the Oracle Inventory path is `/u01/app/oraInventory`. Oracle Universal Installer installs the software in the `ORACLE_BASE` path. If you are performing an Oracle Grid Infrastructure for a Cluster installation, then the Grid installation path is changed to `root` ownership after installation, and the Grid home software location should be in a different path from the Grid user Oracle base.

If you create the OFA path `/u01`, and grant `oracle` 755 permissions to write to that path, then the Oracle Inventory directory is created in the path `/u01/app/oraInventory`, and Oracle Universal Installer creates the path `/u01/app/oracle`, and configures the `ORACLE_BASE` environment variable for the Oracle user to that path. If you are performing an Oracle Database installation, then the Oracle home is installed under the Oracle base. However, if you are installing Oracle Grid Infrastructure for a cluster, then be aware that ownership of the path for the Grid home is changed to `root` after installation and the Grid base and Grid home should be in different locations, such as `/u01/app/23.0.0/grid` for the Grid home path, and `/u01/app/grid` for the Grid base. For example:

```
/u01/app/oraInventory, owned by grid:oinstall
/u01/app/oracle, owned by oracle:oinstall
/u01/app/oracle/product/23.0.0/dbhome_1/, owned by oracle:oinstall
/u01/app/grid, owned by grid:oinstall
/u01/app/23.0.0/grid, owned by root
```

If you have neither set `ORACLE_BASE`, nor created an OFA-compliant path, then the Oracle Inventory directory is placed in the home directory of the user who is performing the installation, and the Oracle software is installed in the path `/app/owner`, where *owner* is the Oracle software installation owner. For example:

```
/home/oracle/oraInventory
/home/oracle/app/oracle/product/23.0.0/dbhome_1
```

Oracle Base Directory Naming Convention

The Oracle Base directory is the database home directory for Oracle Database installation owners, and the log file location for Oracle Grid Infrastructure owners.

Name Oracle base directories using the syntax */pm/h/u*, where *pm* is a string mount point name, *h* is selected from a small set of standard directory names, and *u* is the name of the owner of the directory.

You can use the same Oracle base directory for multiple installations. If different operating system users install Oracle software on the same system, then you must create a separate Oracle base directory for each installation owner. For ease of administration, Oracle recommends that you create a unique owner for each Oracle software installation owner, to separate log files.

Because all Oracle installation owners write to the central Oracle inventory file, and that file mountpoint is in the same mount point path as the initial Oracle installation, Oracle recommends that you use the same */pm/h* path for all Oracle installation owners.

Table D-1 Examples of OFA-Compliant Oracle Base Directory Names

Example	Description
<code>/u01/app/ oracle</code>	Oracle Database Oracle base, where the Oracle Database software installation owner name is <code>oracle</code> . The Oracle Database binary home is located underneath the Oracle base path.
<code>/u01/app/grid</code>	Oracle Grid Infrastructure Oracle base, where the Oracle Grid Infrastructure software installation owner name is <code>grid</code> . Caution: The Oracle Grid Infrastructure Oracle base should not contain the Oracle Grid Infrastructure binaries for an Oracle Grid Infrastructure for a cluster installation. Permissions for the file path to the Oracle Grid Infrastructure binary home are changed to <code>root</code> during installation.



Note:

Oracle home or Oracle base cannot be `symlinks`, nor can any of their parent directories, all the way to up to the `root` directory.

Oracle Home Directory Naming Convention

By default, Oracle Universal Installer configures Oracle home directories using these Oracle Optimal Flexible Architecture conventions.

The directory pattern syntax for Oracle homes is */pm/slu/product/v/type_[n]*. The following table describes the variables used in this syntax:

Variable	Description
<i>pm</i>	A mount point name.
<i>s</i>	A standard directory name.

Variable	Description
<i>u</i>	The name of the owner of the directory.
<i>v</i>	The version of the software.
<i>type</i>	The type of installation. For example: Database (<i>dbhome</i>), Client (<i>client</i>), or Oracle Grid Infrastructure (<i>grid</i>)
<i>n</i>	An optional counter, which enables you to install the same product more than once in the same Oracle base directory. For example: Database 1 and Database 2 (<i>dbhome_1</i> , <i>dbhome_2</i>)

For example, the following path is typical for the first installation of Oracle Database on this system:

```
/u01/app/oracle/product/23.0.0/dbhome_1
```

 **Note:**

Oracle home or Oracle base cannot be `symlinks`, nor can any of their parent directories, all the way to up to the `root` directory.

Optimal Flexible Architecture File Path Examples

Review examples of hierarchical file mappings of an Optimal Flexible Architecture-compliant installation.

```
/u02/u03 /u04
```

 **Note:**

- The Grid homes are examples of Grid homes used for an Oracle Grid Infrastructure for a standalone server deployment (Oracle Restart), or a Grid home used for an Oracle Grid Infrastructure for a cluster deployment (Oracle Clusterware). You can have either an Oracle Restart deployment, or an Oracle Clusterware deployment. You cannot have both options deployed at the same time.
- Oracle Automatic Storage Management (Oracle ASM) is included as part of an Oracle Grid Infrastructure installation. Oracle recommends that you use Oracle ASM to provide greater redundancy and throughput.

Table D-2 Optimal Flexible Architecture Hierarchical File Path Examples

Directory	Description
/	Root directory

Table D-2 (Cont.) Optimal Flexible Architecture Hierarchical File Path Examples

Directory	Description
/u01/	User data mount point 1
/u01/app/	Subtree for application software
/u01/app/ oraInventory	Central OraInventory directory, which maintains information about Oracle installations on a server. Members of the group designated as the OINSTALL group have permissions to write to the central inventory. All Oracle software installation owners must have the OINSTALL group as their primary group, and be able to write to this group.
/u01/app/oracle/	Oracle base directory for user <code>oracle</code> . There can be many Oracle Database installations on a server, and many Oracle Database software installation owners. Oracle software homes that an Oracle installation owner owns should be located in the Oracle base directory for the Oracle software installation owner, unless that Oracle software is Oracle Grid Infrastructure deployed for a cluster.
/u01/app/grid	Oracle base directory for user <code>grid</code> . The Oracle home (Grid home) for Oracle Grid Infrastructure for a cluster installation is located outside of the Grid user. There can be only one Grid home on a server, and only one Grid software installation owner. The Grid home contains log files and other administrative files.
/u01/app/oracle/ admin/	Subtree for database administration files
/u01/app/oracle/ admin/TAR	Subtree for support log files
/u01/app/oracle/ admin/db_sales/	Admin subtree for database named "sales"
/u01/app/oracle/ admin/db_dwh/	Admin subtree for database named "dwh"
/u01/app/oracle/ fast_recovery_are a/	Subtree for recovery files

Table D-2 (Cont.) Optimal Flexible Architecture Hierarchical File Path Examples

Directory	Description
/u01/app/oracle/ fast_recovery_arena/ db_sales	Recovery files for database named "sales"
/u01/app/oracle/ fast_recovery_arena/ db_dwh	Recovery files for database named "dwh"
/u02/app/oracle/ oradata /u03/app/oracle/ oradata /u04/app/oracle/ oradata	Oracle data file directories
/u01/app/oracle/ product/	Common path for Oracle software products other than Oracle Grid Infrastructure for a cluster
/u01/app/oracle/ product/23.0.0/ dbhome_1	Oracle home directory for Oracle Database 1, owned by Oracle Database installation owner account oracle
/u01/app/oracle/ product/23.0.0/ dbhome_2	Oracle home directory for Oracle Database 2, owned by Oracle Database installation owner account oracle
/u01/app/oracle2/ product/23.0.0/ dbhome_2	Oracle home directory for Oracle Database 2, owned by Oracle Database installation owner account oracle2
/u01/app/oracle/ product/23.0.0/ grid	Oracle home directory for Oracle Grid Infrastructure for a standalone server, owned by Oracle Database and Oracle Grid Infrastructure installation owner oracle.

Table D-2 (Cont.) Optimal Flexible Architecture Hierarchical File Path Examples

Directory	Description
/u01/app/23.0.0/ grid	Oracle home directory for Oracle Grid Infrastructure for a cluster (Grid home), owned by user <code>grid</code> before installation, and owned by <code>root</code> after installation.
/u01/app/oracle/ product/23.0.0/ client_1	Oracle home directory for Oracle Database Client 1, owned by Oracle Database installation owner account <code>oracle</code>