Oracle® Fusion Middleware

Error Messages

14c (14.1.2.0.0)
F55371-01
December 2024

Oracle Fusion Middleware Error Messages, 14c (14.1.2.0.0)

F55371-01

Copyright © 2000, 2024, Oracle and/or its affiliates.

Primary Author: Oracle Corporation

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software, software documentation, data (as defined in the Federal Acquisition Regulation), or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs (including any operating system, integrated software, any programs embedded, installed, or activated on delivered hardware, and modifications of such programs) and Oracle computer documentation or other Oracle data delivered to or accessed by U.S. Government end users are "commercial computer software," "commercial computer software documentation," or "limited rights data" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, reproduction, duplication, release, display, disclosure, modification, preparation of derivative works, and/or adaptation of i) Oracle programs (including any operating system, integrated software, any programs embedded, installed, or activated on delivered hardware, and modifications of such programs), ii) Oracle computer documentation and/or iii) other Oracle data, is subject to the rights and limitations specified in the license contained in the applicable contract. The terms governing the U.S. Government's use of Oracle cloud services are defined by the applicable contract for such services. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle®, Java, MySQL, and NetSuite are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Inside are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Epyc, and the AMD logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Contents

Preface

Audience vii
Documentation Accessibility vii
Diversity and Inclusion vii
Conventions vii

1 ADFDI-00100 to ADFDI-55516

2 BEA-000001 to BEA-2194843

3 BRW-15000 to BRW-16976

4 CAPTURE-10000 to CAPTURE-10165

5 CFGFWK-20836 to CFGFWK-64276

6 CHGHOST-20200 to CHGHOST-20219

7 DVT-02012 to DVT-26021

8 EM-00251 to EM-02674

9 ESS-00001 to ESS-09422

10 FRC-60003 to FRC-60108

11 FRM-41480 to FRM-99999

12 GGSTU-60000 to GGSTU-65036

13 IAM-0010002 to IAM-90400084

14 IAU-01023 to IAU-62023

15 INST-01000 to INST-10117

16 J2EE HTTPC-00004 to J2EE HTTPC-12011

17 JPS-00001 to JPS-90642

18 MDS-00001 to MDS-92010

19 NG-1010 to NG-2170

20 OAM-00001 to OAM-36105

21 ODI-1100 to ODI-999999

22 OGGV-00001 to OGGV-600013

23 OHS-03506 to OHS-04533

24 OJRF-00001 to OJRF-00008

25 OWS-00016 to OWS-60003

26 PKI-01001 to PKI-07023

27 RCU-06000 to RCU-07006

28 REP-00001 to REP-80012

29 SDP-26500 to SDP-26236

30 SOAPWS-JMS-225010 to SOAPWS-JMS-225012

31 TCM-00006 to TCM-99009

32 UCM-CS-000001 to UCM-CS-800280

33 UPGAST-00001 to UPGAST-05024

34 UPG-OHS-00001 to UPG-OHS-00013

35 WC-05319 to WC-05370

36 WCC-ADF-10000 to WCC-ADF-30002

37 WCS-03051 to WCS-90200

38 WSM-00001 to WSM-09029

Preface

This document is a reference of the error messages as seen for your Oracle Fusion Middleware component, product, or service.

- Audience
- Documentation Accessibility
- Diversity and Inclusion
- Conventions

Audience

This manual is intended for anyone who uses Oracle Fusion Middleware and requires more information about an error message encountered in the product.

Documentation Accessibility

For information about Oracle's commitment to accessibility, visit the Oracle Accessibility Program website at `http://www.oracle.com/pls/topic/lookup?ctx=acc&id=docacc`.

Accessible Access to Oracle Support

Oracle customers who have purchased support have access to electronic support through My Oracle Support. For information, visit `http://www.oracle.com/pls/topic/lookup?ctx=acc&id=info` or visit `http://www.oracle.com/pls/topic/lookup?ctx=acc&id=trs` if you are hearing impaired.

Diversity and Inclusion

Oracle is fully committed to diversity and inclusion. Oracle respects and values having a diverse workforce that increases thought leadership and innovation. As part of our initiative to build a more inclusive culture that positively impacts our employees, customers, and partners, we are working to remove insensitive terms from our products and documentation. We are also mindful of the necessity to maintain compatibility with our customers' existing technologies and the need to ensure continuity of service as Oracle's offerings and industry standards evolve. Because of these technical constraints, our effort to remove insensitive terms is ongoing and will take time and external cooperation.

Conventions

The following text conventions are used in this document:

Convention	Meaning
boldface	Boldface type indicates graphical user interface elements associated with an action, or terms defined in text or the glossary.
italic	Italic type indicates book titles, emphasis, or placeholder variables for which you supply particular values.
`monospace`	Monospace type indicates commands within a paragraph, URLs, code in examples, text that appears on the screen, or text that you enter.

1
ADFDI-00100 to ADFDI-55516

ADFDI-00100
Unable to send a request for BindingContext: a DIRemoteServlet call is already in progress.

Category:
Session

Cause:
A request to DIRemoteServlet was attempted while another one is already in progress.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00101
unexpected value found in attribute metadata: {0}

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00103
Unable to locate start element: BindingContainer in response stream.

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00105
invalid child element <{0}> encountered within <{1}> element

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00106
missing end element: </{0}>

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00107
row limit exceeded

Category:
Session

Cause:
Too many rows exist in result set.

Action:
Refine your query in order to reduce the number of matching rows.

ADFDI-00108
An attempt to communicate with the server failed since there was no valid user session available.

Category:
Session

Cause:
A valid user session was not available during an attempt to communicate with the server.

Action:
Log in to the server and retry the request. Or, contact the network administrator to review the security configuration.

ADFDI-00109
invalid GetResourceBundle response

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00110
unable to locate element {0} or parse its contents

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00111
unable to create request object

Category:
Session

Cause:
Unable to establish a connection to the DIRemoteServlet.

Action:
Verify that the DIRemoteServlet URL is specified properly and retry request. The system administrator can check the server logs for more information.

ADFDI-00112
unable to create XmlTextWriter

Category:
Session

Cause:
An unexpected error occurred while sending a request to the DIRemoteServlet.

Action:
Retry your request. The system administrator can check the server logs for more information.

ADFDI-00113
unable to get request stream

Category:
Session

Cause:
An unexpected error occurred while sending a request to the DIRemoteServlet.

Action:
Retry your request. The system administrator can check the server logs for more information.

ADFDI-00114
The DIRemoteServlet returned an unrecognized value for element {0}, attribute {1}: {2}.

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00115
The DIRemoteServlet returned an unexpected element type in the response XML: {0}

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00116
The DIRemoteServlet returned invalid XML: unexpected end of response.

Category:
Session

Cause:
An unexpected error occurred while reading the DIRemoteServlet response.

Action:
Retry your request. The system administrator can check the server logs for more information.

ADFDI-00117
The operation cannot be completed due to an unexpected error on the server. Contact your administrator to review the server logs to find more detailed information regarding the cause.

Category:
Session

Cause:
An unexpected error occurred while reading the server response.

Action:
The system administrator can check the server logs for more information.

ADFDI-00118
The DIRemoteServlet returned an error. A subsequent error occurred reading the error details from the response.

Category:
Session

Cause:
An unexpected error occurred while reading the DIRemoteServlet response.

Action:
Retry your request. The system administrator can check the server logs for more information.

ADFDI-00119
The DIRemoteServlet returned an error. A subsequent error occurred reading the error details from the response: unexpected element type: {0}.

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00120
The DIRemoteServlet returned an error. A subsequent error occurred reading the error details from the response: unexpected element name: {0}.

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00121
The expected XML element {0} was not found. Instead, the element {1} of type {2} was found.

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00122
An unexpected XML element name was encountered (expected: {0}, found {1}).

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00123
The expected XML end element {0} was not found. Instead, the element {1} of type {2} was found.

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00124
The expected XML end element {0} was not found. Instead, the element {1} was found.

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00125
The expected XML attribute {0} for element {1} was not found.

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet is invalid.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00126
An attempt was made to set the row position for control binding {0} to {1}. Iterator has {2} rows.

Category:
Session

Cause:
Row index out of bounds.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00127
A version mismatch was detected for {0}. Version {1} was found, version {2} was expected.

Category:
Requests/Responses

Cause:
The servlet version did not match the required level for the client.

Action:
Upgrade the client and/or server so that compatible versions are in use.

ADFDI-00128
unable to locate the column metadata for column with ID: {0}

Category:
Session

Cause:
The binding container metadata did not match the data returned from the server.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00129
invalid Encode URL response

Category:
Session

Cause:
The response received from the server for this request could not be processed. It may be caused by an exception in the server component.

Action:
Retry your request. The system administrator can check the server logs for more information.

ADFDI-00130
The size of requested resource bundle ({1}) exceeds the maximum allowable limit: {0} bytes.

Category:
Files

Cause:
The size of the resource bundle exceeded the supported size.

Action:
Reduce the size of the resource bundle.

ADFDI-00131
The connection attempt has been canceled.

Category:
Session

Cause:
The attempt to connect to the server was canceled.

Action:
Retry the current action.

ADFDI-00132
unable to execute Wininet method {0}; error code: {1}

Category:
Requests/Responses

Cause:
The Wininet library was unable to provide the requested service.

Action:
Retry the current action, confirm connectivity, and/or consult the client logs for more information.

ADFDI-00133
The user session has changed.

Category:
Session

Cause:
The user session timed out or was otherwise invalid.

Action:
Retry the current action, re-login, or re-establish a valid user session.

ADFDI-00134
An attempt to connect to the web application has failed.

Category:
Session

Cause:
The web application may not have been running or may not have been configured to allow client connections.

Action:
Confirm that the web application is accepting connections from a web browser.

ADFDI-00135
The server-side list is not positioned as expected.

Category:
Session

Cause:
The server-side list was not positioned as expected.

Action:
This is an unexpected error condition. The system administrator can check the server logs for more information.

ADFDI-00136
A server side certificate could not be verified. Open Internet Explorer, visit the site that your workbook is attempting to reach, install the certificate, and retry the current action.

Category:
Session

Cause:
A server side certificate could not be verified.

Action:
Open Internet Explorer, visit the site that your workbook is attempting to reach, install the certificate and retry the current action.

ADFDI-00137
The client and server versions are not compatible. Install the client (add-in) that matches the server.

Category:
Deployment

Cause:
The version of the server was not compatible with the version of the client.

Action:
Install the client (add-in) that matches the server. Contact the system administrator and ensure that the client and server versions match.

ADFDI-00138
The current user is not authorized to access the binding container.

Category:
Security

Cause:
The current user did not have the necessary permissions to access the binding container.

Action:
Log out and log back in as a different user, or contact the system administrator to request the necessary permissions.

ADFDI-00139
The setup action has failed unexpectedly. Review the server log files for more information.

Category:
Programmatic

Cause:
The specified setup action failed to execute as expected.

Action:
Review the server logs for more details on the cause of the failure.

ADFDI-00140
An error was encountered while connecting to or communicating with the web application. Details: {0} ({1}: {2}).

Category:
Requests/Responses

Cause:
The client encountered an error when attempting to communicate with the web application.

Action:
Review the server logs for more details on the cause of the failure.

ADFDI-00141
An attempt to establish a user session with the web application has failed.

Category:
Session

Cause:
Something has prevented the client from establishing a valid user session with the web application.

Action:
Obtain and send the Connection Failure Report to the system administrator.

ADFDI-00142
The transaction size limit was exceeded.

Category:
Programmatic

Cause:
Too much data was sent to the server without committing any changes to the database.

Action:
Reduce the amount of pending changes and retry the current action.

ADFDI-00143
Failed to locate metadata.

Category:
Configuration

Cause:
The server could not find the metadata requested by the client.

Action:
Contact the system administrator to make sure the workbook metadata is correctly deployed.

ADFDI-00144
Invalid metadata key

Category:
Configuration

Cause:
The key used to reference the client metadata was invalid.

Action:
Contact the workbook developer to correct the metadata key.

ADFDI-00145
A server-side error has occurred when loading metadata.

Category:
Programmatic

Cause:
A server-side error occurred that prevented the client from loading metadata.

Action:
Review the server logs for more details on the cause of the failure.

ADFDI-00146
Invalid ClientMetadata response

Category:
Session

Cause:
The XML response returned from the DIRemoteServlet was invalid.

Action:
Review the server logs for more details on the cause of the failure.

ADFDI-00147
Create savepoint failed

Category:
Session

Cause:
An unexpected error occurred while creating a savepoint.

Action:
Review the server logs for more details on the cause of the failure.

ADFDI-00148
Restore savepoint failed

Category:
Session

Cause:
An unexpected error occurred while restoring a savepoint.

Action:
Review the server logs for more details on the cause of the failure.

ADFDI-00149
An unexpected exception occurred on the server. Review the server logs for more details on the cause of the failure.

Category:
Programmatic

Cause:
An unexpected error occurred while the server handled a client request.

Action:
Review the server logs for more details on the cause of the failure.

ADFDI-00150
Unexpected Java data type. Name: {0}

Category:
Programmatic

Cause:
An attempt was made to use an unsupported Java data type.

Action:
Replace the unsupported data type with a supported type.

ADFDI-00151
Unable to save connection failure report: {0}.

Category:
Files

Cause:
There was an unexpected exception while attempting to save the connection failure report to the specified file.

Action:
Review the inner exception details to determine root cause.

ADFDI-00152
The business operation, {0}, could not be completed because the attempt to connect to the server failed.

Category:
Session

Cause:
Something has prevented the client from establishing a valid user session with the web application.

Action:
Save and review the connection failure report.

ADFDI-00153
The business operation, {0}, could not be completed because the attempt to connect to the server was canceled.

Category:
Session

Cause:
The user canceled and prevented the client from establishing a valid user session with the web application.

Action:
Save and review the connection failure report.

ADFDI-00500
Unable to execute WinINet method {0}; error code: {1}

Category:
Requests/Responses

Cause:
The WinINet library was unable to provide the requested service.

Action:
Retry the current action, confirm connectivity, and/or consult the client logs for more information.

ADFDI-00501
An unexpected status: {0} ({1}) was returned from the server while requesting the URL: {2}

Category:
Requests/Responses

Cause:
The client was unable to complete its request to the server for the given URL. The server returned an unexpected status code.

Action:
Retry the current action, confirm connectivity, and/or consult the client logs for more information.

ADFDI-00502
The client was unable to establish an unauthenticated session with the web application.

Category:
Requests/Responses

Cause:
An unexpected problem prevented the client from establishing a valid, unauthenticated session with the web application.

Action:
Retry the current action, confirm the authentication configuration and connectivity, and/or consult the client logs and exception details for more information.

ADFDI-00505
An unexpected error has occurred during the current operation. See Details for more information.

Category:
Other

Cause:
There was an unexpected error during the current operation.

Action:
Review configuration and installation. Then, retry the operation.

ADFDI-01001
A validation error occurred for metadata property {0}. Detail: {1}

Category:
Configuration

Cause:
An invalid property value was specified in the configuration metadata.

Action:
Correct the specified property.

ADFDI-01002
A validation warning occurred for metadata property {0}. Detail: {1}

Category:
Configuration

Cause:
An invalid property value was specified in the configuration metadata.

Action:
Correct the specified property.

ADFDI-04000
{0} is installed on this computer with an incompatible installer. Please uninstall the currently installed version and retry the installation with the new installer.

Category:
Installation

Cause:
The product was previously installed with an installation method that is not compatible with the current one.

Action:
Remove the previous installation.

ADFDI-04001
The .NET Framework 4.0 is not installed.

Category:
Installation

Cause:
The .NET Framework 4.0 prerequisite was not installed.

Action:
Install the .NET Framework 4.0.

ADFDI-04002
The Visual Studio 2010 Tools for Office Runtime prerequisite is either not installed or does not meet the minimum required version.

Category:
Installation

Cause:
The Visual Studio 2010 Tools for Office Runtime prerequisite was either not installed or did not meet the minimum required version.

Action:
Install Visual Studio 2010 Tools for Office Runtime.

ADFDI-05002
Unable to locate page definition element in {0}

Category:
Programmatic

Cause:
The root element was missing from the page definition file.

Action:
Ensure that the page definition file is well formed.

ADFDI-05006
A component already exists at origin {0}.

Category:
Programmatic

Cause:
An attempt was made to insert or move a component to a cell that is already in use as the origin of another component.

Action:
Choose a different destination cell for the insertion or move operation.

ADFDI-05012
Unable to locate or open the page definition: {0}. Control bindings are not available for this worksheet. File: {1}.

Category:
Configuration

Cause:
An attempt was made to load the file specified. Either some portion of the file path was invalid, the file did not exist, or the user had insufficient permissions to open the file.

Action:
Ensure that the relevant properties are configured correctly.

ADFDI-05013
There is no page definition selected. Control bindings are not available for this worksheet.

Category:
Configuration

Cause:
User canceled the operation of selecting a page definition.

Action:
Select a valid page definition to associate with the current worksheet.

ADFDI-05016
The workbook, {0}, is missing one or more required settings: ApplicationHomeFolder, WebPagesFolder.

Category:
Configuration

Cause:
The specified workbook was missing one or more settings required for publishing.

Action:
Provide valid values for all settings required for publishing.

ADFDI-05019
The component cannot be placed at the requested location since it would overlap with one or more other components.

Category:
Configuration

Cause:
An attempt was made to place a component in a position that would overlap with other components.

Action:
Choose a different location that will not overlap.

ADFDI-05021
The destination workbook name, {0}, is already being used by an open workbook. The published workbook name cannot be the same as an open workbook even if the directories are different.

Category:
Files

Cause:
The published workbook name was the same as a workbook that was currently open.

Action:
Choose a different name or close the open workbook.

ADFDI-05022
An unexpected exception has occurred. The workbook {0} cannot be published.

Category:
Other

Cause:
An unexpected exception occurred while attempting to publish the workbook.

Action:
Verify settings, installation, and configuration. Then, retry the operation.

ADFDI-05023
There is a mismatch between the destination file extension, {0}, and source file extension, {1}. The workbook cannot be converted during publication.

Category:
Files

Cause:
The publish destination and source workbooks did not have the same file extension.

Action:
Publish the workbook to a file with the same extension. Or, convert the workbook to the desired type before publishing.

ADFDI-05024
This workbook cannot be published because the format is not supported. Use a supported format like 'Excel Workbook (*.xlsx)'.

Category:
Files

Cause:
The source workbook was not a supported file type.

Action:
Convert the workbook to a supported type.

ADFDI-05025
The destination file path exceeds the Excel limit of 219 characters. File path: {0}

Category:
Files

Cause:
The file path length exceeded the length limitation imposed by Microsoft Excel.

Action:
Reduce the length of the path and retry the publish operation.

ADFDI-05026
Cannot publish a customizable workbook to the destination: {0}

Category:
Files

Cause:
The customizable workbook was published to a invalid destination.

Action:
Publish the customizable workbook to a location under the public_html directory of the project associated with current workbook.

ADFDI-05027
Unable to load one or more data binding registry files.

Category:
Files

Cause:
One of more data binding registry files could not be loaded.

Action:
Ensure that the affected files are present at the expected locations.

ADFDI-05500
The attempt to re-establish the server state has failed.

Category:
Data

Cause:
A failed attempt was made to re-establish the server state for a new user session.

Action:
Check the configuration of the workbook to ensure that the attributes and actions used to reestablish the server state are defined correctly. Check the server to determine whether data has been deleted.

ADFDI-05501
The value in the cache was not equal to the attribute value. Attribute binding ID: {0}

Category:
Data

Cause:
The value in the cache was not equal to the attribute value.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05502
Unable to locate control binding {0} in binding container {1}

Category:
Programmatic

Cause:
A failed attempt was made to locate the binding information of a UI component.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05503
An incorrect binding type, {0}, exists for the control binding {1} in the binding container {2}.

Category:
Programmatic

Cause:
The binding type of the component differed from the binding type defined in the binding container.

Action:
Check the configuration of the workbook and retry the operation. Ensure that the control binding type is defined correctly.

ADFDI-05504
Unable to find attribute: {0}

Category:
Programmatic

Cause:
A failed attempt was made to find an attribute in the data context cache.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05505
Unable to find action: {0}

Category:
Programmatic

Cause:
A failed attempt was made to find a restore data context action in the data context cache.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05506
Unable to find list control binding: {0}

Category:
Programmatic

Cause:
A failed attempt was made to locate the list control binding.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05507
Invalid list control binding: {0}

Category:
Programmatic

Cause:
The binding type of the list control was not valid.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05509
Unable to find component: {0}

Category:
Configuration

Cause:
A failed attempt was made to find the binding of the component.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05510
Unable to insert column; column out-of-bounds

Category:
Programmatic

Cause:
A failed attempt was made to insert a dynamic column into the Table because the column was not within the named range.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05511
Unable to remove column; column out-of-bounds

Category:
Programmatic

Cause:
A failed attempt was made to delete a dynamic column into the Table because the column was not within the named range.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05517
Unable to find the control {0} in the binding container.

Category:
Configuration

Cause:
A failed attempt was made to locate the control in the binding container.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05518
Unable to set expression value for read-only expression

Category:
Configuration

Cause:
A failed attempt was made to set the value for a read-only expression.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05519
Unable to find component method, {0}, to invoke.

Category:
Configuration

Cause:
A failed attempt was made to invoke the specified component method.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05524
Unable to position on the current table row.

Category:
Programmatic

Cause:
A failed attempt was made to update the row position in a table for the purpose of invoking an action set on the row.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05529
Unable to load binding container metadata

Category:
Data

Cause:
A failed attempt was made to load the metadata that defines the binding container.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05530
This worksheet, {0}, could not be initialized due to an unexpected error. The worksheet cannot be used.

Category:
Session

Cause:
A failed attempt was made to initialize a worksheet.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05537
The integrity of the workbook integration could not be determined. This workbook cannot be used safely. The integration will now terminate.

Category:
Session

Cause:
The server was unable to read the client registry.

Action:
Verify/correct the client registry in the web application.

ADFDI-05538
The workbook integration has been altered after publishing. It can no longer be used safely. The integration will now terminate.

Category:
Session

Cause:
The tampering check has determined that the workbook has been altered.

Action:
Obtain a fresh, unaltered copy of the published workbbook.

ADFDI-05555
Required property {0} missing for component {1}.

Category:
Programmatic

Cause:
Required component property not defined.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05558
CacheDataContext must specify an action and at least one attribute.

Category:
Configuration

Cause:
The metadata for this worksheet contains one or more invalid CacheDataContext definitions.

Action:
Review and resolve CacheDataContext configuration issues and retry.

ADFDI-05559
Row cache data is invalid.

Category:
Data

Cause:
The row data cached for an ADF Table component is not valid.

Action:
Re-download ADF Table data.

ADFDI-05561
Failed to read multi-sync response as expected.

Category:
Programmatic

Cause:
The number of multi-sync responses did not match the number of multi-sync requests.

Action:
Check your configuration and try the operation again.

ADFDI-05562
Dependent list component has been misconfigured.

Category:
Programmatic

Cause:
The developer has incorrectly configured a list component that depends on another list component.

Action:
Enable verbose logging on the client and review log for additional details on the specific configuration issue.

ADFDI-05563
Restore Server Data Context Cache is corrupted

Category:
Programmatic

Cause:
The hidden cache of data was not in the expected format

Action:
Obtain a new version of the workbook or Clear All Data

ADFDI-05564
The list binding "{0}" has {1} values. Only the first {2} items are stored in the cache.

Category:
Data

Cause:
The number of items in the list exceeded the allowable limit.

Action:
Reduce the number of items in the list. Or, configure the workbook to use a web page dialog for selecting an item from a large list of values.

ADFDI-05565
Unable to retrieve values for the list binding "{0}"

Category:
Programmatic

Cause:
A failed attempt was made to retrieve list values from the server.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05566
Unable to retrieve values for the list binding "{0}", or for one or more of its dependent lists

Category:
Programmatic

Cause:
A failed attempt was made to retrieve list values from the server.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05567
Unable to restore server state. This condition is an unrecoverable error. You will now be logged out of your current session.

Category:
Programmatic

Cause:
The attempt to restore server state failed.

Action:
Log in to the application and retry the operation. Examine the server logs for additional information.

ADFDI-05568
Failed to initialize cache for List binding: {0} in component/column: {1}, owned by type: {2} (in table: {3}).

Category:
Programmatic

Cause:
A failed attempt was made to retrieve and cache list values from the server.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05569
Unable to report table status: status column is not visible.

Category:
Configuration

Cause:
The table was configured so that the Status column is not visible.

Action:
Configure the table so that the Status column is visible.

ADFDI-05570
The Automation API encountered an unexpected condition. Details: {0}

Category:
Configuration

Cause:
The Automation API encountered an unexpected condition.

Action:
Check the configuration of the workbook and/or the automation scripts.

ADFDI-05571
Failed to find resource. Alias: {0} Key: {1}

Category:
Configuration

Cause:
The specified alias-key combination could not be located.

Action:
Check the configuration of the workbook and/or resource files.

ADFDI-05572
Failed to find resource bundle. Alias: {0}

Category:
Configuration

Cause:
The specified resource bundle could not be located.

Action:
Check the configuration of the workbook and/or resource files.

ADFDI-05573
Unable to perform the requested action because the worksheet protection could not be changed.

Category:
Configuration

Cause:
A failed attempt was made to temporarily remove protection from the worksheet.

Action:
Check the protection configuration of the worksheet and retry the operation.

ADFDI-05574
You have modified cells in the key column. This operation can lead to data corruption. Your change will now be reverted.

Category:
Data

Cause:
An attempt was made to modify cells in the key column of an ADF Table.

Action:
Do not modify cells in the key column.

ADFDI-05575
Unable to revert the changes to cells in the key column. The affected table(s) should be considered corrupt. You should revert to a previous version.

Category:
Other

Cause:
A failed attempt was made to revert changes to the key column.

Action:
Obtain a fresh copy of the integrated workbook and re-attempt the operation without modifying cells in the key column.

ADFDI-05576
The action, {0}, cannot be invoked in this context.

Category:
Programmatic

Cause:
An attempt was made to invoke a row-level action in a non-row-level action set.

Action:
Remove this action from this action set.

ADFDI-05577
Failed to retrieve table row data from the server.

Category:
Data

Cause:
A failed attempt was made to retrieve table row data from the server.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05578
The reserved table named range, '{0}', cannot be found or is invalid.

Category:
Configuration

Cause:
A failed attempt was made to access the reserved named range for the table component.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05579
An unexpected error occurred while performing an operation on the table identified by: {0}. Close the workbook without saving it and retry the operation.

Category:
Configuration

Cause:
A failed attempt was made to execute a table operation.

Action:
Close the workbook without saving it and retry the operation.

ADFDI-05580
Unable to bind expression part: {0}

Category:
Configuration

Cause:
A failed attempt was made to bind the expression part.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05581
Unable to write component data into worksheet: {0}

Category:
Programmatic

Cause:
A failed attempt was made to write component data to the worksheet.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-05582
Unable to download flagged rows because the table structure has changed.

Category:
Configuration

Cause:
The DownloadFlaggedRows action was invoked on a table and the column structure is different from when rows were last downloaded.

Action:
Check the configuration of the worksheet.

ADFDI-05584
Unable to convert: '{0}' to the target time zone. Close the workbook without saving it and retry the operation.

Category:
Data

Cause:
An unexpected failure has occurred while converting date time values from one time zone to another.

Action:
Close the workbook without saving it and retry the operation.

ADFDI-05585
The {0} element in the dialog page {1} should be a element; the type <{2}> is not supported.

Category:
Configuration

Cause:
The HTML tag used for the reserved element in the dialog page was not supported.

Action:
Contact the developer of this dialog page to use tag for the reserved element

ADFDI-05586
Failed to hook event handler to the {0} element due to {1}. Closing the dialog with client side scripts is disabled.

Category:
Other

Cause:
Unable to hook an event handler to the reserved html element in the dialog page.

Action:
Close the dialog manually if it is not closed automatically. The developer of this dialog page should avoid using client side scripts to change the value of the reserved element.

ADFDI-05587
The client and server versions do not match. Using this version of the client may result in unexpected behavior or errors.

Category:
Upgrade

Cause:
The client and server versions did not match.

Action:
Install a client that matches the server version.

ADFDI-05588
The number of resource bundles ({1}) exceeds the supported limit of {0}.

Category:
Files

Cause:
The number of resource bundles exceeded the supported limit.

Action:
Reduce the number of resource bundles in this workbook.

ADFDI-05589
You are not authorized to use this worksheet for interacting with the web application.

Category:
Security

Cause:
The current user did not have the necessary permissions to access the page definition file associated with this worksheet.

Action:
Log out and log back in as a different user, or contact the system administrator to request the necessary permissions.

ADFDI-05591
The user session has changed. Re-try the operation.

Category:
Session

Cause:
The user session changed during the execution of an action set.

Action:
The end-user should re-try the operation.

ADFDI-05592
Too much changed data was uploaded.

Category:
Data

Cause:
The amount of changed data that was uploaded exceeds the web application limit.

Action:
Retry the operation with less changed data.

ADFDI-05594
Failed to load the client metadata

Category:
Requests/Responses

Cause:
A failure occured when loading the client metadata

Action:
Check the client and server logs for details about the failure.

ADFDI-05595
DownloadForInsert action ignored for table: {0}. InsertRowEnabled is false.

Category:
Programmatic

Cause:
DownloadForInsert action was included in an action-set, but was not applicable since InsertRowEnabled was false.

Action:
The developer should remove the action, or alter the table so that InsertRowEnabled is true.

ADFDI-05597
Dynamic columns are always visible. Ignoring Visible expression: {0}

Category:
Metadata

Cause:
The workbook configuration specified a Visible expression for a dynamic column

Action:
The developer should adjust the configuration: remove the Visible expression or set Dynamic to True.

ADFDI-05598
TableRowErrorsCache '{0}' is out of space. All previous entries will be purged.

Category:
Other

Cause:
The worksheet storing error message details was out of space.

Action:
No action required.

ADFDI-05599
The source scheme is not supported: {0}.

Category:
Configuration

Cause:
The specified URL had an unsupported scheme.

Action:
The workbook developer should use a URL with a supported scheme.

ADFDI-05600
The URL is invalid: {0}.

Category:
Configuration

Cause:
The specified URL was incorrectly formatted.

Action:
The developer should verify and correct the URL.

ADFDI-05601
Invalid binding attribute {0} in ADF Input Date component/column: {1}.

Category:
Configuration

Cause:
The datatype of binding attribute was not date or datetime.

Action:
Use ADF Input Date only for attributes with date or datetime type.

ADFDI-05602
Unable to capture server state.

Category:
Session

Cause:
The attempt to save the current server state failed.

Action:
Log in to the application and retry the operation. Examine the server logs for additional information.

ADFDI-05603
Unable to create a temporary row.

Category:
Programmatic

Cause:
The attempt to create a temporary row failed.

Action:
Log in to the application and retry the operation. Examine the server logs for additional information.

ADFDI-05604
Unable to launch the update web page in the default web browser. Check the default browser settings and try again.

Category:
Configuration

Cause:
The default web browser could not successfully be launched.

Action:
Check the default browser settings.

ADFDI-05605
Unable to evaluate a nested custom property in EL.

Category:
Configuration

Cause:
A custom property string value referenced in EL was found to contain custom property EL within its value.

Action:
The developer needs to modify the custom property value to remove nested custom property EL.

ADFDI-05606
Status initialized row(s) downloaded into table {0} will be ignored since InsertRowEnabled is false.

Category:
Programmatic

Cause:
One or more status initialized rows were downloaded into the table, but would be ignored since InsertRowEnabled is false.

Action:
The workbook developer should ensure that no status initialized rows are downloaded, or alter the table so that InsertRowEnabled is true.

ADFDI-05607
Unable to load requested resource bundle: {0}.

Category:
Configuration

Cause:
A resource bundle specified in the workbook metadata could not be located/loaded.

Action:
The developer needs to check the configuration of the workbook and ensure that the resource bundle is accessible.

ADFDI-06000
Workbook {0} is not enabled for {1}.

Category:
Files

Cause:
The specified workbook was not the expected type.

Action:
Specify only workbooks enabled for use with this product.

ADFDI-06001
An unexpected exception has occurred. The workbook {0} cannot be published.

Category:
Other

Cause:
An unexpected exception occurred while attempting to publish the workbook.

Action:
Verify settings, installation, and configuration. Then, retry the operation.

ADFDI-06002
Error parsing the command line arguments.

Category:
Configuration

Cause:
The command line arguments were not specified in the correct format.

Action:
Check the usage of the tool and correct the input format.

ADFDI-06003
Unexpected arguments specified: {0}

Category:
Configuration

Cause:
The number of command line arguments exceeded the expected number.

Action:
Specify only the expected arguments.

ADFDI-06005
The source workbook filepath is relative: {0}

Category:
Configuration

Cause:
The source workbook path provided was relative, not absolute.

Action:
Provide a fully-qualified file path.

ADFDI-07507
given buffer size is incorrect; given: {0}

Category:
Data

Cause:
An incorrect value was supplied for the Workbook Parameters buffer size.

Action:
Ensure that compatible versions of the client and server framework are in use. Check the workbook configuration and retry the operation with a different workbook.

ADFDI-07508
did not find expected start tag; found: {0}

Category:
Data

Cause:
The workbook's internal format may be corrupted.

Action:
Ensure that compatible versions of the client and server framework are in use. Check the workbook configuration and retry the operation with a different workbook.

ADFDI-07509
did not find expected end tag; found: {0}

Category:
Data

Cause:
The workbook's internal format may be corrupted.

Action:
Ensure that matching versions of the client and server framework are in use. Check the workbook configuration and retry the operation with a different workbook.

ADFDI-07510
mode length is incorrect; found: {0}

Category:
Data

Cause:
The workbook's internal format may be corrupted.

Action:
Ensure that compatible versions of the client and server framework are in use. Check the workbook configuration and retry the operation with a different workbook.

ADFDI-07511
AppRoot length is incorrect; found: {0}

Category:
Data

Cause:
The workbook's internal format may be corrupted.

Action:
Ensure that compatible versions of the client and server framework are in use. Check the workbook configuration and retry the operation with a different workbook.

ADFDI-07512
Workbook initialization parameters length is incorrect; found: {0}

Category:
Session

Cause:
The workbook's internal format may be corrupted.

Action:
Ensure that compatible versions of the client and server framework are in use. Check the workbook configuration and retry the operation with a different workbook.

ADFDI-07513
Destination length {0} is less than found length {1}.

Category:
Data

Cause:
Internal buffer size mismatch detected.

Action:
Ensure that compatible versions of the client and server framework are in use. Check the workbook configuration and retry the operation with a different workbook.

ADFDI-07516
A worksheet version mismatch was detected in worksheet {0}. Version {1} was found, version {2} was expected.

Category:
Data

Cause:
The workbook's internal format may be corrupted, or incompatible versions of the framework are in use.

Action:
Ensure that compatible versions of the framework are in use; upgrade the workbook and framework.

ADFDI-07517
There are no more rows available in the metadata worksheet {0}.

Category:
Data

Cause:
The maximum capacity for storing metadata has been reached, or the workbook's internal format may be corrupted.

Action:
Remove some components from the workbook in order to free up space.

ADFDI-07518
The workbook has no metadata.

Category:
Data

Cause:
The workbook may be corrupted or the metadata has been erased manually.

Action:
Publish the workbook and try again or contact administrator.

ADFDI-07520
Unable to evaluate the expression '{0}' in '{1}'. Detail: {2}

Category:
Programmatic

Cause:
A failed attempt was made to evaluate an invalid expression.

Action:
Verify and correct the expression.

ADFDI-07521
Unable to evaluate the Excel formula '{0}' in '{1}'. Detail: {2}

Category:
Programmatic

Cause:
A failed attempt was made to evaluate an invalid Excel formula.

Action:
Verify and correct the Excel formula.

ADFDI-07522
Unable to execute the command '{0}' while a cell is in edit mode. Accept or cancel the changes to the current cell and then retry the command.

Category:
Programmatic

Cause:
An attempt was made to invoke a menu or toolbar command while a cell is open in editing mode.

Action:
Accept or cancel the changes to the current cell and then retry the command.

ADFDI-07527
The workbook designer could not initialize due to an unexpected error. The designer cannot be used with this workbook.

Category:
Session

Cause:
A failed attempt was made to initialize the workbook for Design Time mode.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-07528
This workbook could not be initialized due to an unexpected error. The workbook integration cannot be used.

Category:
Session

Cause:
A failed attempt was made to initialize the workbook for Run Time mode.

Action:
Check the configuration of the workbook and retry the operation. Ensure that the web application is running and accepting requests.

ADFDI-07529
An unexpected exception has occurred. The workbook cannot initialize and will now abort.

Category:
Session

Cause:
A failed attempt was made to initialize the workbook for an unknown mode.

Action:
Check the configuration of the workbook and retry the operation.

ADFDI-07530
An unexpected exception has occurred. The workbook cannot switch to test mode.

Category:
Session

Cause:
A failed attempt was made to switch from Design Time mode to Test mode.

Action:
Check the configuration of the workbook and retry the operation. Ensure that the web application is running and accepting requests.

ADFDI-07532
The workbook {0} cannot be used with this installation of {1}.

Category:
Installation

Cause:
An attempt was made to open a design-time or test mode workbook using the add-in installed for runtime use.

Action:
Use only published workbooks with the add-in installed for runtime use. Enable the designer tools in order to use workbooks in other modes.

ADFDI-07538
The Automation API encountered an unexpected condition. Details: {0}

Category:
Programmatic

Cause:
The Automation API encountered an unexpected condition.

Action:
Check the configuration of the workbook and/or the automation scripts.

ADFDI-07541
Unable to write metadata to file: {0}

Category:
Files

Cause:
There was an unexpected exception while attempting to write the XML to the specified file.

Action:
Review the inner exception details to determine root cause.

ADFDI-07542
Unable to import workbook configuration metadata.

Category:
Files

Cause:
There was an unexpected exception while attempting to load the workbook configuration metadata into the current workbook.

Action:
Review the inner exception details to determine root cause.

ADFDI-07543
Unable to import workbook configuration metadata due to schema validation failures.

Category:
Files

Cause:
The attempt to import workbook configuration metadata failed due to XML schema validation failures.

Action:
Review the client logs for detailed information on the schema validation failures and correct the XML.

ADFDI-07544
Unexpected exception during write to metadata cache. The workbook may be corrupted.

Category:
Files

Cause:
The attempt to write workbook configuration metadata failed while writing to the cache.

Action:
Discard the workbook and review the inner exception details to determine root cause.

ADFDI-07545
Unable to display help file.

Category:
Other

Cause:
The attempt to display the help file failed unexpectedly.

Action:
Check the local browser and network settings. Then, retry the operation.

ADFDI-07546
Duplicate component id detected during import: {0}. Replacing with {1}.

Category:
Other

Cause:
A duplicate component id was found.

Action:
Review and update any dependencies on the old component id.

ADFDI-07547
Unable to save diagnostic report: {0}.

Category:
Files

Cause:
There was an unexpected exception while attempting to save diagnostic report to the specified file.

Action:
Review the inner exception details to determine root cause.

ADFDI-07548
The value '{0}' is not valid for the property {1}.

Category:
Configuration

Cause:
The property value entered was not valid.

Action:
Enter a valid property value.

ADFDI-07550
There was a problem loading the user settings file.

Category:
Configuration

Cause:
An unexpected problem prevented the program from properly reading or parsing the user settings file.

Action:
Check whether the file is accessible or has become corrupted. Delete the file and retry the operation.

ADFDI-07551
There was a problem writing to the user settings file.

Category:
Configuration

Cause:
An unexpected problem prevented the program from properly creating and/or writing to the user settings file.

Action:
Check whether the file is accessible and that sufficient disk space is available. Retry the operation.

ADFDI-07553
This workbook contains features that are incompatible with this version of {0}. This workbook will now be disabled.

Category:
Files

Cause:
This workbook was edited by a newer version of ADFdi and includes new features that are incompatible with earlier versions. In rare cases, this condition might be the result of a corrupted workbook.

Action:
Install a newer version of the client and re-open the workbook.

ADFDI-50001
Resource bundle not found. bundle: {0}

Category:
Configuration

Cause:
Unable to load the desired resource bundle class.

Action:
Review the server logs for additional detail on the underlying cause.

ADFDI-50002
Resource key not found. bundle: {0} key: {1}

Category:
Configuration

Cause:
Unable to find the desired key in the bundle.

Action:
Review the server logs for additional detail on the underlying cause.

ADFDI-55000
An unexpected exception occurred on the server. Consult the server logs for more detail.

Category:
Requests/Responses

Cause:
An unexpected condition arose while handling the desktop integration request.

Action:
Review the server logs for additional detail on the underlying cause.

ADFDI-55001
XML element {0} missing required attribute {1}

Category:
Requests/Responses

Cause:
Invalid request XML was received.

Action:
Review the server logs to ensure that only supported clients are accessing the ADFdi Remote Servlet.

ADFDI-55002
The object, {0}, is not available.

Category:
Configuration

Cause:
An expected object was not found or was unavailable.

Action:
Ensure that both the client and server metadata are configured correctly.

ADFDI-55003
The object, {0}, is not available. Name: {1}

Category:
Configuration

Cause:
An expected object was not found or was unavailable.

Action:
Ensure that both the client and server metadata has been configured correctly.

ADFDI-55004
invalid GetResourceBundle request XML

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55005
invalid SyncModel request XML

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55006
unexpected value specified for XML element {0}

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55007
invalid request XML

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55008
invalid request method: {0}

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55009
user session unavailable

Category:
Session

Cause:
The user was not authenticated.

Action:
No action is required.

ADFDI-55010
expected XML element {0}; current element is {1}

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55011
unexpected end-of-file in XML input stream

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55012
invalid XML element: {0}

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55013
expected XML reader state {0}; current state is {1}

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55014
invalid child XML element {1} within XML element {0}

Category:
Requests/Responses

Cause:
The XML request sent by the client was invalid.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55017
The current row count exceeds the configured limit.

Category:
Data

Cause:
The maximum number of rows requested by the client was exceeded.

Action:
Submit a new request that conforms to the limit.

ADFDI-55018
exception occurred while reading an XML request

Category:
Requests/Responses

Cause:
A malformed request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55019
exception occurred while writing the XML response

Category:
Requests/Responses

Cause:
Details about the underlying cause of the error are contained in the server logs.

Action:
Review the server logs for details about additional steps to take.

ADFDI-55021
A version mismatch was detected for {0}. Version {1} was found, version {2} was expected.

Category:
Requests/Responses

Cause:
The client version does not match the required level for the DIRemoteServlet.

Action:
Upgrade the client and/or server so that compatible versions are in use.

ADFDI-55022
invalid SessionStatus request XML

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55023
invalid MultiSyncModel request XML

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55025
The control binding definition for item {0} is incorrect or incompatible. {1}

Category:
Requests/Responses

Cause:
The control binding definition has been misconfigured, or an incompatible control binding has been encountered.

Action:
Check the control binding definition and ensure that only supported control bindings are used.

ADFDI-55026
invalid TamperCheck request XML

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55027
invalid EncodeURL request XML

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55028
unexpected value specified for XML element {0}: {1}

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55030
Cannot find the client registry file: {0}

Category:
Requests/Responses

Cause:
System could not find the client registry file in the web-inf location.

Action:
Contact administrator

ADFDI-55031
An error occurred while trying to read client registry file

Category:
Requests/Responses

Cause:
While trying to read the client registry file, an I/O error occurred.

Action:
Check logs for details of I/O error and address root case to enable file access.

ADFDI-55032
Unable to set attribute {0} (row object unavailable: {1})

Category:
Requests/Responses

Cause:
Client attempted to set an attribute value when no server row is available.

Action:
Refresh the client data and retry the operation.

ADFDI-55033
{0}: cannot convert the input value ({1}) to the expected data type ({2}).

Category:
Requests/Responses

Cause:
The input values were not consistent with expected data type.

Action:
Correct input values according to data type.

ADFDI-55034
Tamper check is disabled.

Category:
Configuration

Cause:
The servlet was configured to disable the tamper check feature.

Action:
Adjust servlet initialization parameters as desired.

ADFDI-55035
Tamper check did not succeed. Result: {0}

Category:
Data

Cause:
Tamper check was unable to match the hashcode of the client to the expected value.

Action:
Adjust the configuration of tamper check or obtain a new copy of the workbook.

ADFDI-55036
Received a request with unexpected content type: {0}

Category:
Requests/Responses

Cause:
A request with an unexpected content type was received.

Action:
Use only supported content types.

ADFDI-55037
Tamper check is configured to allow missing entries.

Category:
Configuration

Cause:
The tamper check feature was configured to allow missing entries.

Action:
Adjust servlet initialization parameters as desired.

ADFDI-55038
The region binding includes an unsupported control type: {0}

Category:
Configuration

Cause:
The page definition was configured to use an unsupported control type.

Action:
Remove the unsupported type.

ADFDI-55039
Unexpected servlet failure

Category:
Requests/Responses

Cause:
The servlet has failed due to an unexpected condition.

Action:
Review the server logs for more information.

ADFDI-55040
Unable to read requested resource bundle: {0}

Category:
Configuration

Cause:
An attempt was made to load a resource bundle that was not available.

Action:
Review the configuration to ensure that the resource bundle is available.

ADFDI-55041
Aborting the commit action for a transaction.

Category:
Data

Cause:
The commit action was aborted for the transaction due to error in the binding container.

Action:
Clear the error conditions and retry the operation.

ADFDI-55042
Unable to set position for {0} with value {1}

Category:
Data

Cause:
A failed attempt was made to position a control binding by attribute value.

Action:
Refresh the client data and retry the operation or review the server logs for more information.

ADFDI-55043
Unable to locate parameter {0} for binding container {1}

Category:
Configuration

Cause:
A failed attempt was made to set a parameter.

Action:
Review the configuration to ensure that the parameter is available.

ADFDI-55044
user session has changed

Category:
Session

Cause:
The client user session timed out or was otherwise invalid.

Action:
Establish a valid user session.

ADFDI-55045
unable to set position to row {0}

Category:
Data

Cause:
A failed attempt was made to position a control binding by row index value.

Action:
Refresh the client data and retry the operation or review the server logs for more information.

ADFDI-55046
A value is required for {0}.

Category:
Data

Cause:
An attempt was made to set an empty value for a mandatory attribute.

Action:
Provide a non-empty value for this property.

ADFDI-55047
retry failed for batch request #{0}

Category:
Requests/Responses

Cause:
A failed attempt was made to retry a successful batch request after restoring to datacontrol savepoint.

Action:
Review the server logs for more details about the cause of the failure.

ADFDI-55048
The current user is not authorized to access the binding container: {0}

Category:
Security

Cause:
The current user did not have the necessary permissions to access the binding container.

Action:
Log out and log back in as a different user, or contact the system administrator to request the necessary permissions.

ADFDI-55049
unable to run the setup action: {0}

Category:
Programmatic

Cause:
The specified setup action was either unavailable on the server or failed with an exception.

Action:
Review the configuration to ensure the setup action id is correct, and see server logs for more details on the cause of failure.

ADFDI-55051
The transaction size limit was exceeded

Category:
Data

Cause:
Too much data was sent to the server without committing any changes to the database.

Action:
Reduce the amount of pending changes and retry the current action.

ADFDI-55052
invalid client metadata request

Category:
Requests/Responses

Cause:
An invalid request was received.

Action:
Review the server logs to ensure that only supported clients are accessing this servlet.

ADFDI-55053
Row changes could not be applied: resubmit the changes.

Category:
Requests/Responses

Cause:
Some other errors prevented the changes for this row from being applied.

Action:
Correct the other errors and retry the operation.

ADFDI-55054
Unable to position a range paging rowset with pending changes.

Category:
Data

Cause:
An attempt was made to navigate a rowset in range paging mode when the rowset has pending changes.

Action:
Commit or rollback pending changes before navigating.

ADFDI-55055
Authorization enforcement has been disabled for this instance of {0}

Category:
Security

Cause:
The web application was configured so that authorization will not be enforced by ADF Desktop Integration.

Action:
Configure the web application so that authorization is enforced by ADF Desktop Integration.

ADFDI-55056
{0} cannot be updated to an error value.

Category:
Data

Cause:
The value entered is an error value.

Action:
Refer to the client documentation for how to resolve the error value.

ADFDI-55057
The value "{0}" cannot be found in the list of items for "{1}".

Category:
Data

Cause:
An attempt was made to set a list to an invalid value.

Action:
Choose a value from the available list of items.

ADFDI-55502
The length of the source data, {0}, is greater than the size of the destination buffer, {1}.

Category:
Data

Cause:
Internal buffer size mismatch was detected.

Action:
Ensure that compatible versions of the client and server framework are in use. Check the workbook configuration and retry the operation with a different workbook.

ADFDI-55510
unable to find expected workbook parameters start tag; found: {0}

Category:
Data

Cause:
The internal format of the workbook might be corrupted.

Action:
Run the workbook admin tool on this workbook. Ensure that compatible versions of the client and server framework are in use.

ADFDI-55511
unable to find expected workbook parameters end tag; found: {0}

Category:
Data

Cause:
The internal format of the workbook might be corrupted.

Action:
Run the workbook admin tool on this workbook. Ensure that compatible versions of the client and server framework are in use.

ADFDI-55512
The workbook parameters buffer size is incorrect: {0}.

Category:
Data

Cause:
The internal format of the workbook might be corrupted.

Action:
Run the workbook admin tool on this workbook. Ensure that compatible versions of the client and server framework are in use.

ADFDI-55513
The workbook parameters mode length is incorrect: {0}.

Category:
Data

Cause:
The internal format of the workbook might be corrupted.

Action:
Run the workbook admin tool on this workbook. Ensure that compatible versions of the client and server framework are in use.

ADFDI-55514
The workbook parameters application root length is incorrect: {0}.

Category:
Data

Cause:
The internal format of the workbook might be corrupted.

Action:
Run the workbook admin tool on this workbook. Ensure that compatible versions of the client and server framework are in use.

ADFDI-55515
The workbook parameters collection length is incorrect: {0}.

Category:
Session

Cause:
The internal format of the workbook might be corrupted.

Action:
Run the workbook admin tool on this workbook. Ensure that compatible versions of the client and server framework are in use.

ADFDI-55516
Unexpected filter failure

Category:
Requests/Responses

Cause:
The filter has failed due to an unexpected condition.

Action:
Review the server logs for more information.

2

BEA-000001 to BEA-2194843

BEA-000001
Server must be started by Node Manager when consensus leasing is enabled.

Category:
ConsensusLeasing

Cause:
The server was not started by Node Manager.

Action:
Start the server using Node Manager.

BEA-000101
Cannot resolve ClusterAddress: {0}

Category:
Cluster

Cause:
The cluster address {0} could not be resolved. ClusterAddress should be a DNS name that maps to multiple IP addresses.

Action:
Set the correct ClusterAddress property for the cluster.

BEA-000102
Joining cluster {0} on {1}:{2}

Category:
Cluster

Cause:
The server has joined cluster {0}.

Action:
No action is required.

BEA-000103
Disconnecting from cluster {0}

Category:
Cluster

Cause:
When a server is suspended, it is no longer a member of cluster {0}.

Action:
No action is required.

BEA-000104
Cluster members are running incompatible versions. Local version: {0}. Remote version ({1}): {2}

Category:
Cluster

Cause:
This server is a different version than other servers in this cluster.

Action:
Ensure that all members of this cluster are running the same version.

BEA-000105
The server is leaving the cluster because it is an incompatible version.

Category:
Cluster

Cause:
This server is running a different version of WebLogic Server.

Action:
Set a different multicast address for this cluster. Use an address in the range of 224.0.0.0 - 239.255.255.255. Avoid the reserved range 224.0.0.0 - 224.0.1.255.

BEA-000107
Failed to install {0} in place of those currently installed due to {1}.

Category:
Cluster

Cause:
An error occurred while resolving non-local conflicting offers for a node in the JNDI tree.

Action:
Check the preceding conflict start message in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-000108
Attempt to retract offer {0}, which is neither installed nor pending.

Category:
Cluster

Cause:
An attempt was made to retract an offer, which was neither previously installed nor is in the conflict resolution stage.

Action:
No action is required.

BEA-000109
An error occurred while sending multicast message: {0}.

Category:
Cluster

Cause:
An error occurred while trying to send a message over multicast.

Action:
WebLogic Server will try to recover from this error. If the problem continues to persist, make sure that the network infrastructure and NIC are functioning properly. If you believe no environment problems exist, contact My Oracle Support and provide the stack trace for further analysis.

BEA-000110
Multicast socket receive error: {0}.

Category:
Cluster

Cause:
An error occurred while trying to receive a message over the multicast.

Action:
Ensure that the NIC is functioning properly. If it appears that no environment problems exist, contact My Oracle Support and provide the stack trace for further analysis.

BEA-000111
Adding {0} with ID:{2} to cluster:{1} view.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000112
Removing {0} with ID:{2} from cluster:{1} view due to timeout.

Category:
Cluster

Cause:
Removing {0} from cluster as it failed to send heartbeats in the past 30 seconds.

Action:
If a server has been shut down or suspended, no action is required. If the remote server {0} appears to be hung, take thread dumps and send them to My Oracle Support.

BEA-000113
Removing {0} from cluster view due to PeerGone.

Category:
Cluster

Cause:
The TCP/IP connection to server {0} was lost.

Action:
If a server has been shut down or suspended, no action is required. If the remote server {0} appears to be hung, take thread dumps and send them to My Oracle Support.

BEA-000114
Failed to find cluster license: {0}

Category:
Cluster

Cause:
A valid license file is required to run clusters.

Action:
Contact an Oracle sales representative for a valid license.

BEA-000115
Lost {0} multicast message(s).

Category:
Cluster

Cause:
This is an informational message. When a server joins a stable cluster, this message will appear since multicast messages sent out by servers in the cluster were not received.

Action:
No action is required.

BEA-000116
Failed to join cluster {0} at address {1} due to: {2}.

Category:
Cluster

Cause:
This happens if you specify an incorrect multicast address for the cluster. Use an address in the range of 224.0.0.0 - 239.255.255.255. Avoid the reserved range 224.0.0.0 - 224.0.1.255.

Action:
Set a valid multicast address and try again.

BEA-000117
Received a stale replication request for object {0}.

Category:
Cluster

Cause:
This happens when a network problem exists, or one of the servers is taking a long time to collect garbage, causing the virtual machine to freeze.

Action:
Tune garbage collection so that it does not pause. If the problem still persists, contact My Oracle Support.

BEA-000118
Lost {0} replication updates of object {1}.

Category:
Cluster

Cause:
If the secondary failed to receive some of the updates, it indicates this to the primary server by causing a NotFoundException to the primary so that the primary server can recreate the session state.

Action:
No action is required.

BEA-000119
Missing multicast address for cluster: {0}. Set the MulticastAddress="a.b.c.d" property for the cluster. Use an address in the range of 224.0.0.0 - 239.255.255.255. Avoid the reserved range 224.0.0.0 - 224.0.1.255.

Category:
Cluster

Cause:
The cluster does not have a defined multicast address.

Action:
Specify a valid multicast address.

BEA-000120
Received error while creating ClusterRuntimeMBean.

Category:
Cluster

Cause:
The JMX framework failed to initialize the ClusterRuntimeMBean.

Action:
Check the cluster configuration. If it appears that there are no configuration problems, contact My Oracle Support.

BEA-000121
Two domains in the same LAN should not use the same multicast address. Domains in conflict are {0} and {1}.

Category:
Cluster

Cause:
Two clusters on the local area network are using the same multicast address.

Action:
Change the multicast address of either domain {0} or {1}.

BEA-000122
Clusters {0} and {1} cannot use the same multicast address.

Category:
Cluster

Cause:
Multiple clusters in the same domain are using the same multicast address.

Action:
For efficiency purposes, use two different multicast addresses.

BEA-000123
Conflict start: You tried to bind an object under the name {0} in the JNDI tree. The object {1} is non-clusterable, and you have tried to bind more than once from two or more servers. Such objects can only be deployed from one server.

Category:
Cluster

Cause:
The cluster is not homogeneous. Two servers in the cluster are providing different services under the same name {0}. If the object is non-clusterable, only one server in the cluster can provide this service.

Action:
There are various options. 1. Make the object clusterable. 2. Change the JNDI name of the object under which it is bound. 3. Make sure the object gets deployed only on one server. 4. Deploy the service on all the servers. However, binding it into the JNDI tree, set the replicate bindings property to false.

BEA-000124
Conflict start: The object {1} you tried to bind under the name {0} in the JNDI tree is clusterable but is incompatible. Ensure that all the servers in the cluster use an identical copy of the object.

Category:
Cluster

Cause:
The object {1} is clusterable. However, it implements different or incompatible interfaces on different servers.

Action:
Ensure that all the servers in the cluster use an identical copy of the object.

BEA-000125
Conflict resolved: {0} for the object {1} under the bind name {0} in the JNDI tree.

Category:
Cluster

Cause:
Corrective action was taken to resolve the conflict.

Action:
No action is required.

BEA-000126
All session objects should be serializable to replicate. Check the objects in the session. Failed to replicate a non-serializable object.

Category:
Cluster

Cause:
Objects in the session are not serializable or externalizable.

Action:
Ensure that all user-defined objects in the HTTP session are serializable.

BEA-000127
Adding {0} to the cluster.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000128
Updating {0} in the cluster.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000129
Removing {0} from the cluster.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required unless you did not shut down a server.

BEA-000133
Waiting to synchronize with other running members of {0}.

Category:
Cluster

Cause:
The cluster member is waiting to synchronize cluster information with other cluster members before completing startup and entering running mode.

Action:
No action is required.

BEA-000137
Error sending multicast message: {0}.

Category:
Cluster

Cause:
The multicast message failed to send due to an IOException.

Action:
Enable cluster debugging to see a detailed message.

BEA-000138
Listening for announcements from cluster {0} on {1}:{2}.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000139
There are two clusters in the network that are possibly running different versions of WebLogic Server. These two clusters probably have the same name {0} and they are using the same address {1} and port {2}.

Category:
Cluster

Cause:
There are two clusters in the network that are possibly running different versions of WebLogic Server. These two clusters probably have the same name {0} and they are using the same address {1} and port {2}.

Action:
Change either the multicast address or the multicast port.

BEA-000140
Failed to deserialize statedump from server {0} with {1}.

Category:
Cluster

Cause:
The server failed to deserialize an object since it does not have the class definition. This usually happens if the application classes are not deployed on all the nodes in the cluster. It is preferable to deploy beans to all the nodes of the cluster.

Action:
Ensure that all the classes are available on all the nodes of the cluster.

BEA-000141
TCP/IP socket failure occurred while fetching state dump over HTTP from {0}.

Category:
Cluster

Cause:
An IOException occurred in the operating system.

Action:
Ensure that no problems exist in the network. If the problem persists, contact My Oracle Support with the stack trace for further analysis.

BEA-000142
Trying to download cluster JNDI tree from server {0}.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000143
Trying to download {1} from a server listening on {0}.

Category:
Cluster

Cause:
This is an informational message.

Action:
If this message continues to appear, ensure that the network is stable. Contact My Oracle Support for further assistance.

BEA-000144
Managed Server {0} has been suspended or shut down.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000145
Managed Server {0} is tagged as a migratable server. A cluster that has migratable servers should configure a JDBC data source to ensure that the migratable server is highly available.

Category:
Cluster

Cause:
The cluster is misconfigured.

Action:
Configure the DataSourceForAutomaticMigration property.

BEA-000147
Server "{0}" failed to renew lease in the {1}.

Category:
Cluster

Cause:
The server failed to renew the lease on time.

Action:
No action is required.

BEA-000148
Migratable server "{0}" is misconfigured. For automatic migration, a pool of machines should be assigned to the cluster or each migratable server in the cluster should have at least a couple of machines assigned to it for automatic migration.

Category:
Cluster

Cause:
The migratable server is misconfigured.

Action:
Ensure that the server is targeted to a machine and restart the migratable server.

BEA-000149
Server failed to get a connection to the {1} during {0}.

Category:
Cluster

Cause:
The database or the consensus leasing basis appears to be down.

Action:
Ensure that the database is accessible to the cluster. In the case of consensus leasing basis the server is in the minority partition and the leasing basis is in some other partition that is not reachable.

BEA-000150
Server failed to get a connection to the {1} in the past {0} seconds for lease renewal. Or, Server could get a connection but failed to renew the lease. Server will shut itself down.

Category:
Cluster

Cause:
The database or consensus leasing basis appears to be down.

Action:
Ensure that the database is accessible to the cluster. In the case of consensus leasing basis, the server is in the minority partition and the leasing basis is in some other partition that is not reachable. If this message continues to appear even when the database is accessible, something may be wrong in the database. Contact My Oracle Support for further assistance.

BEA-000151
Server "{0}" has taken over the role of Cluster Master.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000152
Server "{0}" lost the privileges to be the Cluster Master.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000153
Cluster is misconfigured. For automatic migration, a pool of machines should be assigned to the cluster or each migratable server in the cluster should at least have a couple of machines assigned to it for automatic migration.

Category:
Cluster

Cause:
The cluster is misconfigured.

Action:
Assign a pool of machines for automatic migration and refer to WebLogic Server documentation for more details.

BEA-000154
Cluster is misconfigured. The remote cluster address {0} is not a valid URL.

Category:
Cluster

Cause:
The server is misconfigured.

Action:
Set the correct remote cluster address and restart the servers. If it is not clear on how to set remote ClusterAddress, refer to WebLogic Server documentation.

BEA-000155
Configured cluster address is invalid : {0}. Constructing cluster address dynamically.

Category:
Cluster

Cause:
The cluster configuration is invalid.

Action:
Ensure that the cluster address contains either a DNS name or a comma-separated host list (or IP list) or a comma-separated host:port list (or IP:port list).

BEA-000156
Could not send out new attributes for cluster member {0}: {1}.

Category:
Cluster

Cause:
There was a problem sending out changed member attributes.

Action:
Examine the server logs.

BEA-000158
Server has stopped sending cluster heartbeats and announcements. It is still receiving heartbeats and announcements from other cluster members.

Category:
Cluster

Cause:
The server is going out of the cluster as a result of the suspend or shutdown operation.

Action:
No action is required

BEA-000159
The clocks of the machines hosting local server and remote server "{0}" are off by {1} seconds

Category:
Cluster

Cause:
The clocks of the machines hosting servers in the cluster are not synchronized.

Action:
Ensure that all the machines are synchronized to the same time.

BEA-000160
A request to synchronize the JNDI tree has been made over an insecure channel. Configure a secure HTTP channel for all of the servers in the cluster.

Category:
Cluster

Cause:
The cluster was configured to encrypt multicast data but the request to synchronize the JNDI tree was done on a non-secure channel (HTTP). To secure the cluster completely, configure a secure HTTP channel for all of the servers in the cluster.

Action:
Configure a secure HTTP channel on all of the servers in the cluster.

BEA-000161
Multicast message from server {0} appears to have been tampered with.

Category:
Cluster

Cause:
The authenticity of the message could not be verified.

Action:
Ensure that the network is not being hijacked.

BEA-000162
Starting "{0}" replication service with remote cluster address "{1}"

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000163
Stopping "{0}" replication service

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000164
Synchronized cluster JNDI tree from server {0}.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000165
Some other domain has a cluster that is configured to use the same multicast address and port as a cluster in {0}. Two domains in the same LAN should not use the same multicast address.

Category:
Cluster

Cause:
Two clusters on the local area network are using the same multicast address.

Action:
Change the multicast address of either domain.

BEA-000166
Some other cluster in this domain is configured to use the same multicast address as {0}. Clusters cannot use the same multicast address.

Category:
Cluster

Cause:
Multiple clusters in the same domain are using the same multicast address.

Action:
For efficiency purposes, use two different multicast addresses.

BEA-000167
Some services failed to roll back successfully when trying to abort the migration: {0}.

Category:
Cluster

Cause:
An exception caused the rollback to fail: {0}.

Action:
It would be safest to shut down this server so that any lingering services will stop. They will not be automatically restarted upon reboot. Once the cause of the rollback has been fixed, attempts to migrate to this server should be successful.

BEA-000168
Failed to restart/migrate server "{0}" because of {1}

Category:
Cluster

Cause:
There was an error while restarting migratable server: {1}

Action:
Examine the server logs.

BEA-000170
The server {0} did not receive the multicast packets that it sent.

Category:
Cluster

Cause:
Each WebLogic Server instanec is expected to receive the messages it multicast to its multicast group. Since the server does not receive its own messages, the multicast address configuration in the cluster configuration or the interface address specification may be wrong.

Action:
Ensure that the cluster configuration and server interface configuration are valid

BEA-000171
Failed to load the custom Singleton Services SQL Query Helper: {0}, because of {1}.

Category:
Cluster

Cause:
The most likely cause for failing to load the named class is either a typo in the name of the class or that the class is missing from the server classpath.

Action:
Ensure that the provided classname is valid and that the class exists in the classpath of the server.

BEA-000172
TCP/IP socket failure occurred while fetching state dump over HTTP from {0}. Error message received: {2}. The request was generated by {3}. {1}

Category:
Cluster

Cause:
An IOException occurred in the operating system.

Action:
Ensure that no problems exist in the network. If the problem persists, contact My Oracle Support with the stack trace for further analysis.

BEA-000176
{0} does not specify a machine.

Category:
Cluster

Cause:
{0}'s configuration does not specify the machine on which it is running. Machines must be specified if scripts are to be executed when migrations happen.

Action:
Specify the machine on which {0} is running in the server's console page.

BEA-000178
Failed to execute {0} because of {1}.

Category:
Cluster

Cause:
While trying to run {0}, an exception occurred: {1}.

Action:
Check that the script, {0}, is fully debugged. It may help to run the script by hand to see if any errors are raised.

BEA-000179
{0} failed while altering its lease.

Category:
Cluster

Cause:
An exception occurred: {1}.

Action:
Ensure that, if a database is being used for leasing, it is available.

BEA-000180
Unable to retrieve Job {0} from the database. The retrieval failed with {1}

Category:
Cluster

Cause:
An error occurred while reading a job from the database.

Action:
ENsure that the classes corresponding to the job are present in the server classpath and are of the correct version.

BEA-000182
Job Scheduler created a job with ID {0} for TimerListener with description {1}

Category:
Cluster

Cause:
Job Scheduler created an entry in the database for a submitted job.

Action:
No action is required.

BEA-000183
Successfully cancelled job with ID {0}

Category:
Cluster

Cause:
Job Scheduler removed a job entry from the database based on application request

Action:
No action is required.

BEA-000184
This server did not attempt to renew its lease for {0} seconds. The server may need to be restarted or migrated.

Category:
Cluster

Cause:
The thread that is supposed to regularly renew the lease has become blocked for some reason.

Action:
Ensure that the server is not overloaded with work and that there are enough system resources available on the machine.

BEA-000185
Despite the delay in the lease-renewing thread, the server has successfully renewed its lease. It is no longer in imminent risk of being migrated or restarted.

Category:
Cluster

Cause:
The thread that is supposed to regularly renew the lease became blocked, but is running properly again and has successfully renewed the lease.

Action:
No action is required.

BEA-000186
An error was encountered while migrating {0}: {1}

Category:
Cluster

Cause:
See the error in the message body.

Action:
Ensure that there are enough candidate servers running in the cluster.

BEA-000187
The Singleton Service {0} is now registered on this server. This server may be chosen to host this service.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000188
The Singleton Service {0} is no longer registered on this server.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000189
The Singleton Service {0} is now active on this server.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000190
The Singleton Service {0} has been deactivated on this server.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000191
Now monitoring the Migratable Server {0}

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-000192
A running server was not found to host {0}. The server will retry in a few seconds.

Category:
Cluster

Cause:
All running servers failed when asked to activate {0}.

Action:
Ensure that there is at least one active candidate server for this service and that there is no bug in the activate() method. The service will be tried on all running servers in another few seconds.

BEA-000193
The JTA service for {0} has failed, but {0} is still running. JTA cannot be migrated from a running server.

Category:
Cluster

Cause:
The JTA service failed.

Action:
Check the logs of {0}; {0} should be restarted once the cause of the error has been determined and fixed. Upon restart, the JTA service will be migrated and running transactions recovered.

BEA-000194
An error was encountered while trying to report a migration event: {0}.

Category:
Cluster

Cause:
The most likely cause is the Administration Server being unavailable. If this is intended, this message can be ignored.

Action:
If monitoring information is desired, the Administration Server should be running and reachable.

BEA-000195
An error was encountered while trying to save a migration event. The error was: {0}.

Category:
Cluster

Cause:
An internal WebLogic Server error occurred while trying to create a runtime MBean to encapsulate this data.

Action:
Contact My Oracle Support and provide the stack trace for further analysis.

BEA-000196
Received data about a migration of type {0}, but no such type is recognized by the Administration Server.

Category:
Cluster

Cause:
If the Managed Servers have been upgraded to a newer version of WebLogic Server, they may be reporting data that the Administration Server does not know how to handle.

Action:
Upgrade the Administration Server to the same version as the cluster members.

BEA-000197
Listening for announcements from cluster using unicast cluster messaging

Category:
Cluster

Cause:
Unicast cluster messaging mode is enabled.

Action:
No action is required.

BEA-000198
All replication calls for cluster {0} must be made over channel {1}

Category:
Cluster

Cause:
All replication calls for cluster {0} must be made over channel {1}

Action:
Check the configured channel for replication calls.

BEA-000199
Replication calls can only be made by {0} over {1} channel

Category:
Cluster

Cause:
Replication calls can only be made by {0} over {1} channel

Action:
Check the roles of the users for whom the replication calls are being made.

BEA-000214
WebLogic Server "{1}" version: {0} Copyright (c) 1995,2017, Oracle and/or its affiliates. All rights reserved.

Category:
WebLogicServer

Cause:
The startup banner used when a server starts.

Action:
No action is needed.

BEA-000215
Loaded license: {0}.

Category:
WebLogicServer

Cause:
This prints from the location from which the license file was loaded.

Action:
No action is needed.

BEA-000220
Cannot shut down the server because the request was from a null user (Principal).

Category:
WebLogicServer

Cause:
The server refused to shut down since the command came from an unauthorized user.

Action:
Only users within the Administrators group can shut down the server. Retry the command with a user who has administrator credentials.

BEA-000221
Cannot shut down the server because the request was from a nameless user (Principal).

Category:
WebLogicServer

Cause:
The server refused to shut down since the command came from an unauthorized user.

Action:
Only users within the Administrators group can shut down the server. Retry the command with a user who has administrator credentials.

BEA-000222
Cannot disable server logins because the request was from a null user (Principal).

Category:
WebLogicServer

Cause:
The server refused to lock itself since the command came from an unauthorized user.

Action:
Retry the command with a user who has the privileges necessary to perform this operation.

BEA-000223
Cannot disable server logins because the request was from a nameless user (Principal).

Category:
WebLogicServer

Cause:
The server refused to lock itself since the command came from an unauthorized user.

Action:
Retry the command with a user who has the privileges necessary to perform this operation.

BEA-000224
Cannot enable server logins because the request was from a null user (Principal).

Category:
WebLogicServer

Cause:
The server refused to unlock itself since the command came from an unauthorized user.

Action:
Retry the command with a user who has the privileges necessary to perform this operation.

BEA-000225
Cannot enable server logins because the request was from a nameless user (Principal).

Category:
WebLogicServer

Cause:
The server refused to unlock itself since the command came from an unauthorized user.

Action:
Retry the command with a user who has the privileges necessary to perform this operation.

BEA-000226
The enabling of server logins has been requested by {0}.

Category:
WebLogicServer

Cause:
The server has been requested to unlock itself and enable server logins again.

Action:
No action is needed.

BEA-000227
Server logins have been enabled.

Category:
WebLogicServer

Cause:
Server logins have been enabled.

Action:
No action is needed.

BEA-000228
The disabling of server logins has been requested by {0}.

Category:
WebLogicServer

Cause:
A LOCK command was issued by an administrator.

Action:
No action is needed.

BEA-000229
Server logins have been disabled.

Category:
WebLogicServer

Cause:
A LOCK command was issued by an administrator.

Action:
No action is needed.

BEA-000231
Waiting {0} seconds for server shutdown.

Category:
WebLogicServer

Cause:
A shutdown command was issued with a wait time. The server will wait the specified number of seconds before starting shutdown.

Action:
A cancel shutdown command can be issued during the wait time to cancel the shutdown process. Otherwise no action is needed.

BEA-000232
Server shutdown is commencing now and is irreversible.

Category:
WebLogicServer

Cause:
A shutdown command was issued by an administrator.

Action:
No action is needed.

BEA-000236
Stopping execute threads.

Category:
WebLogicServer

Cause:
An administrator issued a shutdown command.

Action:
No action is needed.

BEA-000238
Shutdown has completed.

Category:
WebLogicServer

Cause:
Shutdown has completed.

Action:
No action needed.

BEA-000240
Cannot cancel the server shutdown because the request was from a null user (Principal).

Category:
WebLogicServer

Cause:
Server shutdown could not be canceled because the user account that was used to issue the cancel command does not have the appropriate privileges.

Action:
The command can only be executed by a user from the administrator group. Retry the command with a user account that has administrator privilieges.

BEA-000241
Cannot cancel the server shutdown because the request was from a nameless user (Principal).

Category:
WebLogicServer

Cause:
Server shutdown could not be canceled because the user account that was used to issue the cancel command does not have the appropriate privileges.

Action:
The command can only be executed by a user from the administrator group. Retry the command with a user account that has administrator privilieges.

BEA-000242
Cannot cancel server shutdown because there is no shutdown in progress.

Category:
WebLogicServer

Cause:
The server shutdown cannot be canceled as the server is not in the state 'Shutdown in Progress'.

Action:
No action is needed. Check the Administration Console for the state of the server.

BEA-000243
It is too late to cancel the server shutdown because the shutdown is already in progress.

Category:
WebLogicServer

Cause:
The server has already started to shut down. It is too late to cancel shutdown at this point.

Action:
No action is needed.

BEA-000244
Canceling server shutdown.

Category:
WebLogicServer

Cause:
An administrator has issued a cancel shutdown operation.

Action:
No action is needed.

BEA-000246
Server shutdown has been canceled and logins are enabled.

Category:
WebLogicServer

Cause:
The cancel shutdown operation was successful.

Action:
No action is needed.

BEA-000248
An exception occurred while trying to find a localized T3Srvr message, message ID {0}, {1}

Category:
WebLogicServer

Cause:
The localized version of the message could not be found.

Action:
No action is required.

BEA-000249
Because the weblogic.ConsoleInputEnabled property is set to true, the server can only be shut down from the command line. Type the command "shut" in the window in which the server was started.

Category:
WebLogicServer

Cause:
The weblogic.ConsoleInputEnabled property was set true on the server startup command line.

Action:
To shut down the server, type the command "shut" in the window in which the server was started.

BEA-000251
The server switched to the group "{0}".

Category:
WebLogicServer

Cause:
A non-privileged group was specifed. The server switched to the specified group after starting.

Action:
No action is needed.

BEA-000252
Cannot switch to the group "{0}". {1}

Category:
WebLogicServer

Cause:
The server was unable to switch to the specified group.

Action:
Ensure that the specified group exists.

BEA-000253
Switched to the user "{0}".

Category:
WebLogicServer

Cause:
A non-privileged user was specified. The server switched to the specified user after starting.

Action:
No action is needed.

BEA-000254
Cannot switch to the user "{0}". {1}

Category:
WebLogicServer

Cause:
The server could not switch to the specified non-privileged user.

Action:
Ensure that the specified user exists.

BEA-000256
Invoking {0}.main({1})

Category:
WebLogicServer

Cause:
The server configuration specifies startup and shutdown classes to run.

Action:
No action is required.

BEA-000257
Exception reading command: {0}

Category:
WebLogicServer

Cause:
An exception occurred while reading commands from the shell window.

Action:
Disable the shell command input property weblogic.ConsoleInputEnabled.

BEA-000258
Command [{0}]

Category:
WebLogicServer

Cause:
The Administration Console received the specified command and is about to execute it.

Action:
No action is needed.

BEA-000259
Administration Console: profiling enabled.

Category:
WebLogicServer

Cause:
Profiling has been enabled in the Administration Console.

Action:
No action is needed.

BEA-000260
Administration Console: profiling disabled.

Category:
WebLogicServer

Cause:
Profiling has been disabled in the Administration Console.

Action:
No action is required.

BEA-000261
The system user is not permitted to shut down, {0}.

Category:
WebLogicServer

Cause:
The server was not shut down because the user is not authorized to shut down the server.

Action:
See the exception text in {0} for more information on diagnosing the problem. See the previous log messages for more information on authorization failure. If the user does not have permission to shut down the server, but should, use the Administration Console to define a policy for this server that allows the user to shut down.

BEA-000262
No such command: {0}.

Category:
WebLogicServer

Cause:
The unknown command was entered.

Action:
Refer to the list of known commands.

BEA-000263
GC: before free/total={0}/{1} ({2}%).

Category:
WebLogicServer

Cause:
The GS statistics are shown before forcing GC.

Action:
No action is needed.

BEA-000264
GC: after free/total={0}/{1} ({2}%).

Category:
WebLogicServer

Cause:
The GS statistics are shown after forcing GC.

Action:
No action is needed.

BEA-000265
Attempt to unbind ClientContext "{0}" that is not bound.

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000266
{0} has {1,choice,1#one pending ExecuteRequest|2#{1,number} pending ExecuteRequests}.

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000267
{0} had a negative workQueueDepth of {1}.

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000268
Failed to send unsolicted message "{0}" to client, {1}

Category:
WebLogicServer

Cause:
Deprecated functionality

Action:
Deprecated functionality

BEA-000269
The connection to the client using "{0}" has been unexpectedly lost due to {1}. The server is initiating a hard disconnect.

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000270
Timing out "{0}" because it was idle.

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000271
Ignoring a repeated request to schedule the death of "{0}".

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000272
Scheduling the death of "{0}".

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000273
Removing "{0}" because of hard disconnect timeout.

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000274
Removing "{0}" because of soft disconnect timeout.

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000275
Soft disconnect pending for {0,choice,0#less than a minute|1#one minute|2#{0} minutes}.

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000276
Hard disconnect pending for {0,choice,0#less than a minute|1#one minute|2#{0} minutes}.

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000277
Idle disconnect pending for {0,choice,0#less than a minute|1#one minute|2#{0} minutes}.

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000283
Failed to marshal response, {0}

Category:
WebLogicServer

Cause:
Deprecated functionality

Action:
Deprecated functionality

BEA-000284
Unexpected failure to marshal response, {0}

Category:
WebLogicServer

Cause:
Deprecated functionality

Action:
Deprecated functionality

BEA-000286
Failed to invoke startup class "{0}", {1}.

Category:
WebLogicServer

Cause:
An exception occurred in a startup class.

Action:
Determine the error in the startup class code and restart the server. To work around the problem, set the "abort on startup failure" property to false.

BEA-000287
Invoking startup class: {0}.startup({1}).

Category:
WebLogicServer

Cause:
The startup class was invoked with the specified arguments.

Action:
No action is needed.

BEA-000288
{0} reports: {1}.

Category:
WebLogicServer

Cause:
The return value of the startup class was logged.

Action:
No action is needed.

BEA-000289
Failed to invoke shutdown class "{0}", {1}.

Category:
WebLogicServer

Cause:
An exception occurred in a shutdown class.

Action:
Determine the error in the shutdown class code and restart the server.

BEA-000290
Invoking shutdown class: {0}.shutdown({1}).

Category:
WebLogicServer

Cause:
The server is invoking shutdown classes as a part of shutdown.

Action:
No action is needed.

BEA-000291
{0} reports: {1}.

Category:
WebLogicServer

Cause:
The server logs the return value of the shutdown class.

Action:
No action is needed.

BEA-000297
Inconsistent security configuration, {0}

Category:
WebLogicServer

Cause:
An exception occurred in SSL initialization.

Action:
Look at the exception in {0} for more information on diagnosing the problem.

BEA-000298
Certificate expires in {0} days: {1}

Category:
WebLogicServer

Cause:
The certificate is about to expire.

Action:
Obtain a new server certificate or trusted CA certificate before it expires.

BEA-000306
Cannot use SSL because no certificates have been specified in the WebLogic Server configuration.

Category:
WebLogicServer

Cause:
No certificates can be found for use by SSL.

Action:
If using a keystore for the server certificate, set the ServerPrivateKeyAlias in the SSL MBean. If using the Server Certificate File, ensure that valid certificates are contained within the file.

BEA-000307
Exportable key maximum lifespan set to {0} uses.

Category:
WebLogicServer

Cause:
The server logs the exportable key maximum lifespan so it is clear what lifespan is being used.

Action:
Verify that the lifespan is the desired value.

BEA-000314
The execution class "{0}" did not retrieve a T3Executable or T3ExecutableLazy.

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000315
Unexpected failure of T3ExecutableLazy, {0}

Category:
WebLogicServer

Cause:
This is an informational message.

Action:
No action is required.

BEA-000316
enableWatchDog() is not permitted from within a server.

Category:
WebLogicServer

Cause:
Deprecated functionality

Action:
Deprecated functionality

BEA-000317
disableWatchDog() is not permitted from within a server.

Category:
WebLogicServer

Cause:
Deprecated functionality

Action:
Deprecated functionality

BEA-000320
Error creating runtime MBean for execute queue {0}.

Category:
WebLogicServer

Cause:
An internal system error occurred.

Action:
Contact My Oracle Support with the server logs.

BEA-000329
Started the WebLogic Server Administration Server "{0}" for domain "{1}" running in production mode.

Category:
WebLogicServer

Cause:
The production mode of the server is enabled.

Action:
Set the weblogic.ProductionModeEnabled property of the domain in the startup script to change the server mode.

BEA-000330
Started the WebLogic Server Managed Server "{0}" for domain "{1}" running in production mode.

Category:
WebLogicServer

Cause:
The production mode of the server is enabled.

Action:
Set the weblogic.ProductionModeEnabled property of the domain in the startup script file to change the server mode.

BEA-000331
Started the WebLogic Server Administration Server "{0}" for domain "{1}" running in development mode.

Category:
WebLogicServer

Cause:
The production mode of the server is disabled (default).

Action:
Set the weblogic.ProductionModeEnabled property of the domain in the configuration script to change the server mode.

BEA-000332
Started the WebLogic Server Managed Server "{0}" for domain "{1}" running in development mode.

Category:
WebLogicServer

Cause:
The production mode of the server is disabled (default).

Action:
Set the weblogic.ProductionModeEnabled property of the domain in the startup script to change the server mode.

BEA-000333
Queue usage is greater than QueueLengthThresholdPercent "{0}%" of the maximum queue size. An attempt will be made to allocate ThreadsIncrease "{1}" thread(s) to help.

Category:
WebLogicServer

Cause:
The server is under high load.

Action:
Review the execute queue settings.

BEA-000337
{0} has been busy for "{1}" seconds working on the request "{2}", which is more than the configured time (StuckThreadMaxTime) of "{3}" seconds in "{4}". Stack trace: {5}

Category:
WebLogicServer

Cause:
The server is extremely busy or the thread is hung.

Action:
Monitor the method that the hung thread is running. Use the Administration Console monitor execute request feature or take a thread dump (weblogic.Admin THREAD_DUMP).

BEA-000339
{0} has become "unstuck".

Category:
WebLogicServer

Cause:
A thread previously stuck is now available.

Action:
No action is needed.

BEA-000342
Unable to initialize the server: {0}.

Category:
WebLogicServer

Cause:
An exception occurred during the server initialization.

Action:
Analyze the weblogic.log file to determine why the server did not initialize completely.

BEA-000343
The health monitor for "{0}" failed to register because of exception "{1}".

Category:
WebLogicServer

Cause:
Refer to the exception printed in the log message.

Action:
Refer to the exception printed in the log message.

BEA-000344
The health monitor for "{0}" failed to unregister because of exception "{1}".

Category:
WebLogicServer

Cause:
Refer to the exception printed in the log message.

Action:
Refer to the exception printed in the log message.

BEA-000345
******* * * The selected version of Java, {0}, contains a known security flaw. Please upgrade to at least {1} * *******

Category:
WebLogicServer

Cause:
JEP-290 support is missing.

Action:
Upgrade the version of Java used to run WebLogic Server.

BEA-000357
Started WebLogic Server independent Managed Server "{0}" for domain "{1}" running in development mode.

Category:
WebLogicServer

Cause:
The server started with the Managed Server independence mode enabled.

Action:
No action is required.

BEA-000358
Started WebLogic Server independent Managed Server "{0}" for the domain "{1}" running in production mode.

Category:
WebLogicServer

Cause:
The production mode of the server is enabled.

Action:
Set the ProductionModeEnabled property of the domain in the configuration file to change the server mode.

BEA-000360
The server started in {0} mode.

Category:
WebLogicServer

Cause:
The startup mode was set to SUSPENDED.

Action:
No action is required.

BEA-000362
Server failed. Reason: {0}

Category:
WebLogicServer

Cause:
Inspect the log file for indications of the root cause of the failure.

Action:
Inspect the log file for indications of the root cause of the failure.

BEA-000365
Server state changed to {0}.

Category:
WebLogicServer

Cause:
The server progressed through the startup or shutdown sequence.

Action:
No action is required.

BEA-000366
The server failed to shut down. Exception: {0}

Category:
WebLogicServer

Cause:
Inspect the log file for indications of the root cause of the failure.

Action:
Inspect the log file for indications of the root cause of the failure.

BEA-000371
An error occurred during server shutdown: {0}.

Category:
WebLogicServer

Cause:
Inspect the log file for indications of the root cause of the failure.

Action:
Inspect the log file for indications of the root cause of the failure.

BEA-000374
Waiting for ExecuteQueue {0} to finish {1} pending requests.

Category:
WebLogicServer

Cause:
The server found pending requests in one of the execute queues while suspending. The server will wait for the requests to complete.

Action:
No action is required.

BEA-000377
Starting WebLogic Server with {0} Version {1} from {2}.

Category:
WebLogicServer

Cause:
The server is starting.

Action:
No action is needed.

BEA-000378
The server failed to shut down within the configured timeout of {0} seconds. The server process will now exit.

Category:
WebLogicServer

Cause:
Forced shutdown is taking too long to complete.

Action:
No action is needed.

BEA-000381
ServerLifeCycle operation failed. Message: {0} {1}

Category:
WebLogicServer

Cause:
A server operation, such as shutdown, failed.

Action:
If the error is not application related, contact My Oracle Support.

BEA-000382
A critical service failed. The server will automatically transition to the ADMIN state.

Category:
WebLogicServer

Cause:
A server lifecycle operation or a critical service failed.

Action:
The server logs contain information about the failure. If the error is not application related, contact My Oracle Support.

BEA-000383
A critical service failed. The server will shut itself down.

Category:
WebLogicServer

Cause:
A critical service failed.

Action:
The server logs contain information about the failure. If the error is not application related, contact My Oracle Support.

BEA-000384
A fatal configuration failure occurred during startup. Check if the config.xml file contains invalid entries. Reason: {0}

Category:
WebLogicServer

Cause:
The server failed to start due to invalid configuration.

Action:
Check if the config.xml file contains invalid entries. Contact My Oracle Support for more information.

BEA-000385
Server health failed. Reason: {0}

Category:
WebLogicServer

Cause:
Inspect the log file for indications of the root cause of the failure.

Action:
Inspect the log file for indications of the root cause of the failure.

BEA-000386
Server subsystem failed. Reason: {0}

Category:
WebLogicServer

Cause:
Inspect the log file for indications of the root cause of the failure.

Action:
Inspect the log file for indications of the root cause of the failure.

BEA-000388
JVM called the WebLogic Server shutdown hook. The server will force shutdown now.

Category:
WebLogicServer

Cause:
The JVM called the WebLogic Server shutdown hook. The server will force shutdown now.

Action:
No action is needed.

BEA-000394
Deadlock detected: {0}.

Category:
WebLogicServer

Cause:
There are threads deadlocked in the server.

Action:
Report this error to My Oracle Support if the deadlock involves WebLogic Server internal code.

BEA-000395
The following extensions directory contents added to the end of the classpath: {0}.

Category:
WebLogicServer

Cause:
Extensions directory contents were added to the classpath.

Action:
No action is needed.

BEA-000396
Server {0} has been requested by {1}.

Category:
WebLogicServer

Cause:
A request was made to perform the specified server operation.

Action:
No action is needed.

BEA-000398
Secure mode enabled for WebLogic Server "{0}".

Category:
WebLogicServer

Cause:
Secure mode is enabled.

Action:
None.

BEA-000401
Socket queue full, dropping socket {0}.

Category:
Socket

Cause:
The internal queue for socket read requests is full. Additional read requests for sockets will be dropped.

Action:
Check for other log messages that give more information about the failure.

BEA-000402
There are: {0} active sockets, but the maximum number of socket reader threads allowed by the configuration is: {1}. The configuration may need altered.

Category:
Socket

Cause:
When non-native I/O is used, I/O is performed in a blocking manner. Therefore, if the number of socket reader threads is less than the number of active sockets, performance may degrade significantly.

Action:
Optimally, increase the ThreadPoolPercentSocketReaders, or the ThreadPoolSize, or both. Optimally, decrease the SocketReaderTimeoutMinMillis, or the SocketReaderTimeoutMaxMillis, or both.

BEA-000403
IOException occurred on socket: {0} {1}.

Category:
Socket

Cause:
An unexpected IOException occurred while performing I/O for the socket.

Action:
Check network connectivity. If the situation persists after environmental issues are resolved, contact My Oracle Support.

BEA-000404
ThreadDeath in processSockets {0}.

Category:
Socket

Cause:
A ThreadDeath error occurred while processing sockets.

Action:
Check for other log messages that give more information about the failure.

BEA-000405
Uncaught Throwable in processSockets {0}.

Category:
Socket

Cause:
A Throwable was caught while processing sockets.

Action:
Check for other log messages that give more information about the failure.

BEA-000406
{0}

Category:
Socket

Cause:
This is an informational message.

Action:
No action is required.

BEA-000409
Problem on socket: {0} {1}

Category:
Socket

Cause:
An exception occurred while registering the socket with the muxer. It is possible that the file descriptor cannot be obtained from the socket.

Action:
Capture the errors and send the server log files to My Oracle Support.

BEA-000414
Could not initialize the POSIX performance pack.

Category:
Socket

Cause:
The shared library for the POSIX performance pack could not be loaded.

Action:
Ensure that the muxer shared library (libmuxer.so) exists in a directory that is in the LD_LIBRARY_PATH. If the situation persists, contact My Oracle Support.

BEA-000415
System has file descriptor limits of soft: {0}, hard: {1}

Category:
Socket

Cause:
This is an informational message.

Action:
No action is required.

BEA-000416
Using effective file descriptor limit of: {0} open sockets and files.

Category:
Socket

Cause:
This is an informational message.

Action:
No action is required.

BEA-000421
Uncaught Throwable in processSockets {0}.

Category:
Socket

Cause:
A Throwable was caught while processing sockets.

Action:
Check for other log messages that give more information about the failure.

BEA-000429
Muxer received error: {0} {1}.

Category:
Socket

Cause:
An unexpected error occurred while processing socket I/O requests.

Action:
Capture the errors and send the server log files to My Oracle Support.

BEA-000431
Accepted connection: filtering is set to: "{0}", remote address: "{1}", remote port: "{2,number,0}", local address: "{3}", local port: "{4,number,0}", protocol: "{5}"

Category:
Socket

Cause:
This is an informational message for the administrator.

Action:
No action is required.

BEA-000432
Unable to load performance pack. Using Java I/O instead. {0}

Category:
Socket

Cause:
The native library for the performance pack was unable to be loaded.

Action:
Ensure that the classpath and the environment is set up properly. If the situation persists, contact My Oracle Support.

BEA-000435
Unable to initiate read for the socket. The maximum allowed number of pending I/O requests ({0}) has been exceeded.

Category:
Socket

Cause:
The maximum allowed number of pending I/O requests ({0}) has been exceeded. Further read requests for the socket cannot be initiated.

Action:
Check for other log messages that give more information about the failure.

BEA-000436
Allocating {0} reader threads.

Category:
Socket

Cause:
This is an informational message.

Action:
No action is required.

BEA-000437
The default setting for MuxerClass was overridden and no muxer class name was specified. Resorting to implementation class: {0}.

Category:
Socket

Cause:
This is an informational message.

Action:
No action is required.

BEA-000438
Unable to load performance pack. Using Java I/O instead. {0}

Category:
Socket

Cause:
The native performance pack was unable to be loaded.

Action:
Ensure that the appropriate path for the native libraries is set properly in the environment.

BEA-000439
Unable to create the Java socket muxer.

Category:
Socket

Cause:
Creation of the Java socket muxer failed.

Action:
Ensure that the classpath is set properly.

BEA-000440
Unable to initiate I/O for {0} {1}.

Category:
Socket

Cause:
The initiation of the I/O operation failed, which could have been caused by the network, I/O or other problems.

Action:
Correct any conditions as suggested by the error message, if applicable.

BEA-000441
Unable to find internal data record for the socket {0}, with I/O completion result {1}

Category:
Socket

Cause:
The internal data record for the socket could not be found while completing an I/O operation.

Action:
Check for other log messages that give more information about the failure.

BEA-000442
The connection attempt was rejected because the incoming protocol is not enabled on channel "{0}".

Category:
Socket

Cause:
The connection attempt was rejected because a protocol was not enabled for this server, as determined by the ServerMBean, or was not enabled on this particular channel.

Action:
Enable the protocol on the channel.

BEA-000443
The connection attempt was rejected because the incoming protocol {1} is not enabled on channel {0}.

Category:
Socket

Cause:
The connection attempt was rejected because the {1} protocol was not enabled for this server, as determined by the ServerMBean, or was not enabled on this particular channel.

Action:
Enable the {1} protocol on the channel.

BEA-000444
Could not load the performance pack that can take advantage of the /dev/(e)poll device due to: {0}. Will attempt to use the performance pack that does not depend on the /dev/(e)poll device.

Category:
Socket

Cause:
The operating system does not support the /dev/(e)poll or the device is not initialized.

Action:
Ensure that the operating system supports the /dev/(e)poll device.

BEA-000445
Connection rejected, filter blocked {0}, {1}

Category:
Socket

Cause:
The incoming message was not recognized as one of the supported protocols.

Action:
Ensure that the server is configured for the relevant protocol.

BEA-000446
Native I/O enabled.

Category:
Socket

Cause:
This is an informational message.

Action:
No action is required.

BEA-000447
Native I/O disabled. Using Java I/O.

Category:
Socket

Cause:
This is an informational message.

Action:
No action is required.

BEA-000448
Socket channel support has been enabled for a JVM on which the feature is unsupported.

Category:
Socket

Cause:
This error is caused by turning on a feature that is not supported on the underlying JVM.

Action:
Either disable socket channel support or use a JVM version on which this feature is supported.

BEA-000449
Closing the socket, as no data read from it on {1}:{2} during the configured idle timeout of {0} seconds.

Category:
Socket

Cause:
The WebLogic Server instance or the network may be overloaded, which is causing the socket to idle timeout.

Action:
Capacity tuning of the server is required.

BEA-000451
Closing the socket, as end of file is encountered while reading from the socket to the ONS server at {0}.

Category:
Socket

Cause:
The connection to the remote Oracle Notification Server (ONS) process might have been disconnected.

Action:
Check the status of the remote ONS process.

BEA-000452
An exception occurred on the socket to the ONS server at {0}: {1}.

Category:
Socket

Cause:
An exception occurred while reading from the socket. The connection to the remote Oracle Notification Server (ONS) process might have been disconnected.

Action:
Check the network connectivity to the remote ONS process. If the situation persists after environmental issues are resolved, contact My Oracle Support.

BEA-000453
An exception occurred while processing the message sent from the ONS at {0}: {1}

Category:
Socket

Cause:
An error occurred while parsing the message received from the remote ONS.

Action:
Check the ONS log file for additional details.

BEA-000454
Unable to establish connection to the remote ONS process at {0}:{1}. Exception occurred while doing handshake: {2}

Category:
Socket

Cause:
An exception occurred while doing handshake with the remote ONS process.

Action:
Check the exception and ONS log file for additional details.

BEA-000455
Attempting to remove unregistered HandshakeCompletedListener: class={0}, instance={1}.

Category:
Socket

Cause:
The unregistered HandshakeCompletedListener: class={0}, instance={1}, is attempting to be removed.

Action:
The unregistered HandshakeCompletedListener: class={0}, instance={1}, is attempting to be removed.

BEA-000456
Unable to load performance pack. Using Java I/O instead.

Category:
Socket

Cause:
The native library for the performance pack could not be loaded.

Action:
Ensure that the classpath and the environment is set up properly. If the situation persists, contact My Oracle Support.

BEA-000457
NIOInputStream received error while closing java.nio.channels.Selector: : {0} {1}.

Category:
Socket

Cause:
An unexpected error occurred while processing socket I/O requests.

Action:
If the situation persists, capture the errors and send the server log files to My Oracle Support.

BEA-000458
{0}

Category:
Socket

Cause:
See the message body.

Action:
Review the message body to determine the appropriate action to take.

BEA-000501
Peergone send failed - target unreachable.

Category:
RJVM

Cause:
This is an informational message.

Action:
No action is required.

BEA-000502
Peergone send failed - target already gone.

Category:
RJVM

Cause:
This is an informational message.

Action:
No action is required.

BEA-000503
Incoming message header or abbreviation processing failed. {0}

Category:
RJVM

Cause:
While processing an incoming message an error was encountered. It is likely that the message was corrupted.

Action:
This is most likely a temporary situation. No action is required. If this situation continues, contact My Oracle Support with the server logs and configuration.

BEA-000504
Unmarshal exception: received illegal command code: {0}

Category:
RJVM

Cause:
A message containing an invalid command code was received. This message cannot be processed. One of the possible reasons is that the message was corrupted in transit.

Action:
This is most likely a temporary situation. No action is required. If this situation continues, contact My Oracle Support with the server logs and configuration.

BEA-000505
Peer did not send us a valid heartbeat interval; using the default heartbeat specified as a property.

Category:
RJVM

Cause:
The incoming message has an invalid heartbeat interval. This is either due to message corruption in transit or to an invalid choice for the heartbeat interval on the peer that is attempting to establish communication with this JVM.

Action:
If the peer that is attempting to establish communication is overriding the default heartbeat interval, ensure that a valid interval is used. If not, contact My Oracle Support with the server logs and configuration.

BEA-000506
Closing: {0} because of {1}

Category:
RJVM

Cause:
This JVM has received an incoming message that is incompatible with the way the protocols are supposed to work.

Action:
This is most likely a temporary situation. No action is required. If this situation continues, contact My Oracle Support with the server logs and configuration.

BEA-000507
Could not create/send request to close duplicate connection message. {0}

Category:
RJVM

Cause:
Creation or sending of the message to request closing a connection caused an I/O error.

Action:
This is most likely a temporary situation. No action is required. If this situation continues, contact My Oracle Support with the server logs and configuration.

BEA-000508
ID: {0} in use by: {1}, can not install {2}

Category:
RJVM

Cause:
The ID {0} is already associated with and in use by {1} and hence cannot be used in association with {2}.

Action:
Ensure that unique IDs are used in registration.

BEA-000509
Finder not initialized.

Category:
RJVM

Cause:
This JVM was created without a valid finder.

Action:
Ensure that a valid finder is used when creating this JVM.

BEA-000510
Unsolicited response: {0}

Category:
RJVM

Cause:
A duplicate response has been received for a request that has already received its response.

Action:
This is most likely a temporary situation. No action is required. If this situation continues, contact My Oracle Support with the server logs and configuration.

BEA-000511
Unsolicited error response for: {0}

Category:
RJVM

Cause:
A duplicate error response was received for a request that has already received its response or its error response.

Action:
This is most likely a temporary situation. No action is necessary. If this situation continues, contact My Oracle Support with the server logs and configuration.

BEA-000512
New heartbeat period: {0} is different from established heartbeat period: {1}; using established heartbeat period

Category:
RJVM

Cause:
This is an informational message.

Action:
No action is required.

BEA-000513
Failure in heartbeat trigger for RJVM: {0}. {1}

Category:
RJVM

Cause:
This error indicates a temporary failure in the heartbeat trigger mechanism.

Action:
No action is required. This is usually a temporary failure.

BEA-000514
openConnection() failed. {0}

Category:
RJVM

Cause:
Possible causes are an invalid target address or the target not being active or reachable.

Action:
This is most likely a temporary situation. No action is required. If this situation continues, contact My Oracle Support with the server logs and configuration.

BEA-000515
execute failed {0}

Category:
RJVM

Cause:
A failure was encountered when handling the incoming HTTP message.

Action:
This is most likely a temporary situation. No action is required. If this situation continues, contact My Oracle Support with the server logs and configuration.

BEA-000519
Unable to connect to a remote server on address {1} and port {2,number,0} with protocol {0}. The exception is {3}

Category:
RJVM

Cause:
The target is either not reachable or is not active.

Action:
Ensure that the target is active.

BEA-000570
Network Configuration for Channel "{0}" Listen Address {1} Public Address {2} Http Enabled {3} Tunneling Enabled {4} Outbound Enabled {5} Admin Traffic Enabled {6} ResolveDNSName Enabled {7}

Category:
RJVM

Cause:
This is an informational message.

Action:
No action is required.

BEA-000572
The server rejected a connection attempt {0} probably due to an incorrect firewall configuration or administrative command.

Category:
RJVM

Cause:
The incoming connection attempt was probably made through an address translating firewall. WebLogic Server needs to be correctly configured for this to work. This message can also occur if an administration connection attempt, requiring administrator level security, is made on a non-administrative port.

Action:
Configure the public and private addresses for this WebLogic Server instance to reflect the configuration of the firewall. The private address is the actual address the server is running. The public address is the address that external clients use to connect.

BEA-000573
RequestTimeout for message id {0} with message: {1}.

Category:
RJVM

Cause:
The server timed out while waiting for a response to a request. The configured timeout may not be sufficient enough for the runtime environment.

Action:
Consider raising the value of the "weblogic.jndi.responseReadTimeout" property.

BEA-000574
Bootstrap to {0} failed. The remote side declared peer may be gone on this JVM.

Category:
RJVM

Cause:
Bootstrapping to the remote address has failed likely due to a PeerGone on this JVM.

Action:
Check whether the remote server is up and running

BEA-000577
Unable to get weblogic.rjvm.WebRjvmSupport.webRjvmSupport from HK2 services. exception: {0}

Category:
RJVM

Cause:
weblogic.rjvm.WebRjvmSupport is not registered as an HK2 service.

Action:
Contact My Oracle Support with the server logs and configuration.

BEA-000578
Unable to load weblogic.rjvm.WebRjvmSupport.webRjvmSupport. exception: {0}

Category:
RJVM

Cause:
Class weblogic.servlet.internal.utils.WebRjvmSupportImpl can be loaded.

Action:
Contact My Oracle Support with the server logs and configuration.

BEA-000579
Failed to get client certificate. exception: {0}

Category:
RJVM

Cause:
Failed to get client certificate. exception: {0}

Action:
Check the custom class which is specified by the system property weblogic.security.SSL.ClientCertPlugin.

BEA-000580
Failed to send {0}. {1}

Category:
RJVM

Cause:
While sending a message an error was encountered.

Action:
This is most likely a temporary situation. No action is required. If this situation continues, contact My Oracle Support with the server logs and configuration.

BEA-000600
Callback {0} failed: {1}

Category:
Common

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000601
AdminProxyWatchDog: Enabled. Interval = {0} secs.

Category:
Common

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000602
AdminProxyWatchDog: Enable failed.

Category:
Common

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000603
AdminProxyWatchDog: Disabled.

Category:
Common

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000604
AdminProxyWatchDog: Disable failed.

Category:
Common

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000605
Connectivity lost to WatchDog Client. Shutting down.

Category:
Common

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000606
AdminProxyWatchDog: No echo received in last {0} minutes. Shutting down.

Category:
Common

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000607
AdminProxyWatchDog: Echo Received.

Category:
Common

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000608
AdminProxyWatchDog: Tick. diff = {0}

Category:
Common

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000609
An error occurred during server shutdown: {0}.

Category:
Common

Cause:
The indicated error has occurred while the server was shutting down.

Action:
Check for other log messages that give more information about the failure.

BEA-000610
Expected RemoteException, RuntimeException, or Error {0}

Category:
Common

Cause:
An unexpected low-level message was sent to the server.

Action:
This is likely due to an internal client/server error that should be reported to My Oracle Support.

BEA-000611
No resources in the pool {0} will be tested, as specified MaxUnavailable {1} has been reached.

Category:
Common

Cause:
The application MaxUnavailable attribute for this pool has been configured. Since the number of unavailable resources in the pool has reached or exceeded the configured limit, no more resources will be tested (as resources become unavailable to the application during the testing).

Action:
If necessary, tune the value for the MaxUnavailable attribute for the pool.

BEA-000612
All {1} resource instances currently available in the pool {0} are being tested.

Category:
Common

Cause:
This is a warning indicating that all currently available resources in the pool are being tested. Therefore, some or all of them may become unavailable to the application for a short time.

Action:
Reduce the current setting of the MaxUnavailable attribute for the pool.

BEA-000613
Testing of resources upon creation has been dynamically enabled for pool "{0}".

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000614
Testing of resources upon creation has been dynamically disabled for pool "{0}".

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000615
Testing of resources when being reserved has been dynamically disabled for pool "{0}".

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000616
Testing of resources when being reserved has been dynamically enabled for pool "{0}".

Category:
Common

Cause:
This is an informational message.

Action:
No action required.

BEA-000617
Testing of resources when being released has been dynamically enabled for pool "{0}".

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000618
Testing of resources when being released has been dynamically disabled for pool "{0}".

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000619
Unable to forcibly release resource "{1}" back into the pool "{0}". Received exception: {2}.

Category:
Common

Cause:
As part of the InactiveResourceTimeout feature, resources that are found to be inactive for the configured period of time are forcibly released back into the pool. The operation could not be performed for the indicated reason.

Action:
Contact My Oracle Support.

BEA-000620
Forcibly releasing inactive resource "{1}" back into the pool "{0}".

Category:
Common

Cause:
The resource was found to be unused by the application for the specified duration, and hence is being forcibly released back into the pool.

Action:
Check application code for leakages of resource objects, or tune the configured value of the relevant pool attribute.

BEA-000621
Expected RemoteException, RuntimeException, or Error {0}

Category:
Common

Cause:
An unexpected low-level message was sent to the server.

Action:
This is likely to be due to an internal server/client error that should be reported to My Oracle Support.

BEA-000622
Ignoring attempt to release resource "{1}" to pool "{0}" after the pool has been shut down.

Category:
Common

Cause:
Application is trying to release a resource to a pool after the pool has been shutdown.

Action:
Check application behaviour. All resources should be closed before the application is shutdown.

BEA-000623
Setting CapacityIncrement for pool "{0}" to 1. The specified value of "{1}" is not valid.

Category:
Common

Cause:
The application had specified an invalid value for CapacityIncrement.

Action:
Check and correct the specified value for CapacityIncrement for the indicated pool.

BEA-000624
Setting frequency of testing of free resources in pool "{0}" to 5 seconds, since the specified value of "{1}" is not valid.

Category:
Common

Cause:
The application had specified an invalid value for the test frequency.

Action:
Check and correct the specified value for TestFrequencySeconds for the indicated pool.

BEA-000625
The application has disabled periodic testing of free resources in pool "{0}".

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000626
Free resources in pool "{0}" will be tested every "{1}" seconds.

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000627
Reached maximum capacity of pool "{0}", making "{2}" new resource instances instead of "{1}".

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000628
Created "{1}" resources for pool "{0}", out of which "{2}" are available and "{3}" are unavailable.

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000629
Recreated "{2}" out of "{1}" resources for pool "{0}".

Category:
Common

Cause:
As part of forcibly suspending a pool, all resources currently in use are destroyed and recreated. This message indicates that not all required resources were recreated.

Action:
Contact My Oracle Support.

BEA-000630
Unable to create "{1}" resources for pool "{0}".

Category:
Common

Cause:
As part of the ConnectionCreationRetry feature, pools periodically attempt to create unavailable resources. This message indicates that in the current attempt, the indicated number of resources could not be created.

Action:
Check whether the failure condition that prevents the resources from being created (for example, the database server or downed network connectivity to it) is still persisting.

BEA-000631
Unknown resource "{1}" being released to pool "{0}": {2}

Category:
Common

Cause:
Application is trying to release a resource to a pool that is no longer part of the pool. This could happen if the pool was forcibly suspended (which results in all borrowed resources being closed and replaced with new ones) while the resource was borrowed by the application.

Action:
Check application behavior.

BEA-000632
Resource Pool "{0}" shutting down, ignoring {1} resources still in use by applications..

Category:
Common

Cause:
The administrator is shutting down the pool while applications are still using resources that they have obtained from the pool. It is possible that these resources may have been leaked by the applications.

Action:
Check application behavior.

BEA-000633
Resource Pool "{0}" suspending due to consecutive number of resource creation failures exceeding threshold of {1}

Category:
Common

Cause:
Resource creation or resource tests have repeatedly failed.

Action:
Determine the cause of resource failures and take corrective action.

BEA-000634
Resource hang detected for pool "{0}", group "{1}". Waited {2} milliseconds where a typical test has been taking {3}.

Category:
Common

Cause:
Resource tests have been taking longer than expected.

Action:
Correct the condition that causes the resource tests to block for extended periods of time.

BEA-000635
Resource Pool "{0}", group "{1}" disabled due to number of resource creation or test failures exceeding threshold of {2}.

Category:
Common

Cause:
Resource creation or resource tests have repeatedly failed.

Action:
Determine the cause of resource failures and correct.

BEA-000636
Resource Pool "{0}", group "{1}" enabled.

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000637
Resource Pool "{0}" resuming due to successful resource creation or test.

Category:
Common

Cause:
This is an informmational message.

Action:
No action is required.

BEA-000638
Resource Pool "{0}" is being suspended by an external command (multi data source or console or other).

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000639
Resource Pool "{0}" is being force-suspended by an external command (multi data source or console or other).

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000640
Resource Pool "{0}" resuming by external command (multi data source or console or other).

Category:
Common

Cause:
This is an informational message.

Action:
No action is required.

BEA-000701
Unable to mount the fileSystem named {0} {1}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000702
Unable to unmount the fileSystem named {0} {1}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000703
Unable to get fileSystem context from Root {0}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000704
Cannot create file system at {0} {1}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000705
Created file system at {0}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000706
Unable to find remote file {0} {1}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000707
Unable to open remote file {0} {1}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000708
T3RemoteOutputStreamProxy: write timed out or interrupted - {0}, {1}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000709
T3RemoteOutputStreamProxy: flush timed out or interrupted - {0}, {1}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000710
TimeRepeat trigger scheduled to run at a date in the past : {0}, trigger will not repeat

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000711
Uncaught throwable in run {0}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000712
Exception invoking {0} {1}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000713
Exception closing stream {0}

Category:
T3Misc

Cause:
Deprecated functionality.

Action:
Deprecated functionality.

BEA-000800
{0} stopped.

Category:
Kernel

Cause:
A ThreadDeath exception caused a shutdown.

Action:
No action is required.

BEA-000801
ExecuteRequest: {0} cancelled.

Category:
Kernel

Cause:
This only happens when WebLogic Server is used in conjunction with an IDE, which uses JVMDI to cancel in-flight requests. If this occurs in normal operation, contact My Oracle Support.

Action:
No action is required.

BEA-000802
ExecuteRequest failed {0}.

Category:
Kernel

Cause:
An execute request generated an exception that was not handled.

Action:
Contact My Oracle Support.

BEA-000803
The Class {0} has a setter {1} for attribute {2} which does not have a constructor that could be initialized from a String value of {3}.

Category:
Kernel

Cause:
No constructor that takes a String argument was found for the declared attribute type.

Action:
Provide a constructor with a String argument.

BEA-000804
The Class {0} attribute {1} could not be initialized with value {2}. The exception message is {3}.

Category:
Kernel

Cause:
See the exception stack trace for details.

Action:
Take the appropriate action based on the error message.

BEA-000805
The self-tuning thread pool is disabled. An execute queue will be created for each Work Manager definition.

Category:
Kernel

Cause:
The server is starting.

Action:
No action is required.

BEA-000807
Work Manager {0} has reached its capacity. It is rejecting from thread {1}. The message is {2}. Throwable is {3}.

Category:
Kernel

Cause:
This is a Work Manager bug.

Action:
No action is required.

BEA-000808
The executing thread is a non-WebLogic Server thread. Modify the application to use the Commonj Work Manager API.

Category:
Kernel

Cause:
The use of an application spawned a Java thread instead of the Commonj Work Manager API.

Action:
Modify the application to use the Commonj Work Manager APIs.

BEA-000810
The memory pressure field has changed from {0} to {1}.

Category:
Kernel

Cause:
The memory pressure in the system has gone either up or down.

Action:
The system should be responding to the memory pressure level. No further action should be taken.

BEA-000902
A duplicate expression was found in the system property {0}.nonProxyHosts: {1}.

Category:
Net

Cause:
The system property {0}.nonProxyHosts contains a pipe character delimited list of hosts, which should be connected to directly and not through the proxy server.

Action:
Check the system property {0}.nonProxyHosts. The value can be a list of hosts, each separated by a |. In addition, a wildcard character (*) can be used for matching. For example: -D{0}.nonProxyHosts="*.foo.com|localhost".

BEA-000903
Failed to communicate with proxy: {0}/{1}. Will try connection {2}/{3} now.

Category:
Net

Cause:
An IOException was received while communicating with the proxy server.

Action:
Check the exception for more information. Check if the proxy is running by pinging the proxy: {0}/{1} from the same machine.

BEA-000904
{0} initializing the URL stream handler with custom factory: {1}.

Category:
Net

Cause:
The factory class that was specified against the system property weblogic.net.http.URLStreamHandlerFactory failed to load or invoke.

Action:
Check the system property weblogic.net.http.URLStreamHandlerFactory. This property is used to set a custom URLStreamHandlerFactory.

BEA-000905
Could not open connection with host: {0} and port: {1}.

Category:
Net

Cause:
The connection attempt failed.

Action:
Ensure that the server is running on the specified host and port.

BEA-000906
Failed to communicate with proxy: {0}/{1}.

Category:
Net

Cause:
An IOException was received while communicating with the proxy server.

Action:
Check the exception for more information. Check if the proxy is running by pinging the proxy: {0}/{1} from the same machine.

BEA-001035
The following error has occurred: {0}.

Category:
JDBC

Cause:
The embedded message should contain an explanation of the failure.

Action:
Take appropriate action based on the reported error.

BEA-001058
Could not get JNDI context: {0}

Category:
JDBC

Cause:
Look at the printed exception to see why the call failed.

Action:
Correct the problem and re-run the operation.

BEA-001064
Ignoring the property "enableTwoPhaseCommit" for JDBCTxDataSource "{0}". This property is used only for those drivers that do not natively support XA.

Category:
JDBC

Cause:
The property EnableTwoPhaseCommit was configured to "true" for an XADataSource and will be ignored.

Action:
No action is required.

BEA-001066
Delaying {0,number} seconds before making a {1} pool connection.

Category:
JDBC

Cause:
Some databases cannot handle a tight loop of making multiple connections from one application. If this is the case and the delay is more than 2 seconds, this message will be printed.

Action:
No action is required.

BEA-001067
Connection for pool "{0}" refreshed.

Category:
JDBC

Cause:
A connection for the specified pool has been refreshed.

Action:
No action is required.

BEA-001068
Connection for pool "{0}" created.

Category:
JDBC

Cause:
A connection for the specified pool has been created.

Action:
No action is required.

BEA-001072
Connection for XA pool "{0}" created.

Category:
JDBC

Cause:
A connection for the specified XA pool has been created.

Action:
No action is required.

BEA-001073
Connection for XA pool "{0}" refreshed.

Category:
JDBC

Cause:
A connection for the specified XA pool has been refreshed.

Action:
No action is required.

BEA-001074
A JDBC pool connection leak has been detected. A connection leak occurs when a connection obtained from the pool was not closed explicitly by calling close() and then was disposed by the garbage collector and returned to the data source connection pool. The following stack trace at create shows where the leaked connection was created. {0}

Category:
JDBC

Cause:
A JDBC pool connection leak was detected. A connection leak occurs when a connection obtained from the pool was not closed explicitly by calling close() and then was disposed by the garbage collector and returned to the data source connection pool. A stack trace is printed indicating where the leaked connection was created.

Action:
Close the connection appropriately.

BEA-001076
An attempt has been made to release a connection that belongs to a non-existing pool. Ensure that the pool "{0}" has been destroyed by intent.

Category:
JDBC

Cause:
An attempt was made to release a connection that belongs to a non-existing pool.

Action:
Correct the destroy operation to specify a valid pool name.

BEA-001083
Multi data source "{0}" was created with {1,number} connection pools for {2}.

Category:
JDBC

Cause:
A multi data source was created with the specified number of connection pools.

Action:
No action is required.

BEA-001084
Multi data source "{0}" will be shutdown

Category:
JDBC

Cause:
The specified multi data source is being shut down.

Action:
No action is required.

BEA-001086
Data source "{0}" with JNDI name "{1}" will be shut down.

Category:
JDBC

Cause:
The specified data source is being shut down.

Action:
No action is required.

BEA-001089
Data source connection pool {0} has been started for application {1}, module {2}.

Category:
JDBC

Cause:
The specified data source connection pool is being started.

Action:
No action is required.

BEA-001099
Data source connection pool "{0}" reset by "{1}".

Category:
JDBC

Cause:
The specified connection pool has been reset.

Action:
No action is required.

BEA-001100
Data source connection pool "{0}" shut down by "{1}".

Category:
JDBC

Cause:
The specified data source connection pool has been shut down, as requested by the application.

Action:
No action is required.

BEA-001101
Data source connection pool "{0}" disabled by "{1}".

Category:
JDBC

Cause:
The specified data source connection pool has been disabled.

Action:
No action is required.

BEA-001102
Data source connection pool "{0}" enabled by "{1}".

Category:
JDBC

Cause:
The specified data source connection pool has been enabled.

Action:
No action is required.

BEA-001104
A globally scoped data source connection pool named ({0}) already exists.

Category:
JDBC

Cause:
When adding or referencing a JDBC data source connection pool that is an application-scoped pool, a globally scoped data source connection pool with the same name already exists. The locally scoped pool has precedence over the global pool.

Action:
If you want to reference the global pool in your application, the name of the global pool or the application-scoped pool must be changed to be unique.

BEA-001105
Referenced global pool ({0}) has the same name as a locally defined data source connection pool or data source ({1}).

Category:
JDBC

Cause:
When deploying a JDBC data source connection pool (not application-scoped) an application (locally) scoped data source connection pool with the same name already exists. The locally scoped pool has precedence over the global pool.

Action:
If you want to reference the global pool in your application, the name of the global pool or the application-scoped pool must be changed to be unique.

BEA-001107
There is a globally defined data source ({0}) with the same JNDI name ({1}) as a locally defined data source.

Category:
JDBC

Cause:
It is possible to use a resource descriptor with application-scoped pools. If the local JNDI lookup reveals that there is a pool with the JNDI name that is specified in the resource descriptor, it is assumed that this is a pool that the application meant to use and it is bound into comp/env. However, a check in the global namespace indicates that there is also a global pool with the same JNDI name.

Action:
If you want to reference the global pool in your application, the JNDI name of the global pool or the application-scoped pool must be changed to be unique.

BEA-001108
A locally scoped pool ({0}) was bound into comp/env with the JNDI name ({1}).

Category:
JDBC

Cause:
It is possible to use a resource descriptor with application-scoped pools. If the local JNDI lookup reveals that there is a pool with the JNDI name specified in the resource-descriptor, it is assumed that this is the pool that the application meant to use and it is bound into comp/env.

Action:
No action is required. If this association is not desired, specify a unique JNDI name in the resource descriptor.

BEA-001109
A globally scoped pool ({0}) was bound into comp/env with the JNDI name ({1}).

Category:
JDBC

Cause:
It is possible to use a resource descriptor with global data source connection pools. If the JNDI lookup reveals that there is a pool with the JNDI name that is specified in the resource descriptor, it is assumed that this is the pool that the application was meant to use and it is bound into comp/env.

Action:
No action is required. If this association is not desired, specify a unique JNDI name in the resource descriptor.

BEA-001110
No test table set up for pool "{0}". Connections will not be tested.

Category:
JDBC

Cause:
TestConnectionsOnReserve, TestConnectionsOnRelease, TestConnectionsOnCreate, TestFrequencySeconds were configured but TestTableName was not configured.

Action:
Configure a valid TestTableName for the data source connection pool.

BEA-001111
Unable to verify the test "{1}" set up for pool "{0}". Connections will not be tested. The test will not be used by isValid either.

Category:
JDBC

Cause:
While creating a data source connection pool with the attributes specified to test the pool connections, a test is run during the pool initialization. This test failed with the printed error.

Action:
Check the SQL error that occurred and correct the problem. The specified TestTableName might not exist.

BEA-001112
Test "{1}" set up for pool "{0}" failed with exception: "{2}".

Category:
JDBC

Cause:
The specified data source connection pool has been configured with one or more attributes to test the pool connections. One of those test attempts failed. The associated error is printed.

Action:
Check the associated error to see what the problem is and correct it. Normally, this indicates that a connection was lost to the database (the database is down). This needs to be corrected by the database administrator.

BEA-001113
Data source connection pool "{0}" shrunk by "{1}".

Category:
JDBC

Cause:
The data source connection pool has been shrunk by the specified amount as requested by the application.

Action:
No action is required.

BEA-001114
Soft shutdown called on data source connection pool "{0}" by "{1}".

Category:
JDBC

Cause:
A soft shutdown operation on the specified data source connection pool has been started, as requested by the application.

Action:
No action is required.

BEA-001115
Hard shutdown called on data source connection pool "{0}" by "{1}".

Category:
JDBC

Cause:
A hard shutdown operation on the specified data source connection pool has been started, as requested by the application.

Action:
No action is required.

BEA-001116
Disable and freeze users called on data source connection pool "{0}" by "{1}".

Category:
JDBC

Cause:
An operation to disable and freeze users on the specified data source connection pool has been started, as requested by the application.

Action:
No action is required.

BEA-001117
Disable and drop users called on data source connection pool "{0}" by "{1}".

Category:
JDBC

Cause:
An operation to disable and drop users on the specified data source connection pool has been started, as requested by the application.

Action:
No action is required.

BEA-001118
Unable to register for receiving MBean notifications of dynamic configurations changes for data source connection pool "{0}": "{1}". Pool will not be dynamically reconfigured.

Category:
JDBC

Cause:
The server was unable to register for receiving MBean notifications of dynamic configurations changes for the specified data source connection pool. The connection pool will not be dynamically reconfigured.

Action:
Check the exception that is printed along with this message to see what the cause of the failure was.

BEA-001119
Unable to delete configuration MBean for pool "{0}": "{1}"

Category:
JDBC

Cause:
While doing a forced shutdown, the data source connection pool was removed but the associated MBean for the connection pool was not removed.

Action:
Check the exception that is printed along with this message to see what the cause of the failure was.

BEA-001120
Created data source named {0} for Pool {1}.

Category:
JDBC

Cause:
There was a user request to create a data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001121
Created TX data source named {0} for Pool {1}.

Category:
JDBC

Cause:
The user requested that the TX data source be created, either implicitly or explicitly.

Action:
No action is required.

BEA-001122
Destroyed TX data source named {0} for Pool {1}.

Category:
JDBC

Cause:
There was a user request to destroy the TX data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001123
Destroyed data source named {0} for Pool {1}.

Category:
JDBC

Cause:
There was a user request to destroy the data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001124
Created Connection Pool named {0}.

Category:
JDBC

Cause:
There was a user request to create the data source connection pool, either implicitly or explicitly.

Action:
No action is required.

BEA-001125
Created multi data source named {0}.

Category:
JDBC

Cause:
There was a user request to create the multi data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001126
Destroyed Connection Pool named {0}.

Category:
JDBC

Cause:
There was a user request to destroy the data source connection pool, either implicitly or explicitly.

Action:
No action is required.

BEA-001127
Destroyed multi data source named {0}.

Category:
JDBC

Cause:
There was a user request to destroy the multi data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001128
Connection for pool "{0}" has been closed.

Category:
JDBC

Cause:
A connection for the specified data source connection pool has been closed.

Action:
No action is required.

BEA-001129
Received exception while creating connection for pool "{1}": {0}.

Category:
JDBC

Cause:
The exception message should indicate the probable cause of the error.

Action:
Check the error to see why the connection creation failed and correct the problem.

BEA-001130
Disabled statement caching for connection in pool "{0}" as it is using the WebLogic Type-2 XA driver.

Category:
JDBC

Cause:
Statement caching was disabled for the specified data source connection pool because it is using the WebLogic Type-2 XA driver. This driver has a limitation based on the implementation using the ORACLE OCI interface. Cursors are closed when the XAResource.end is called, causing all prepared statements to be no longer valid.

Action:
No action is required. Use a different driver if you want to use the prepared statement cache with the driver.

BEA-001131
Received an exception when closing a cached statement for the pool "{0}": {1}.

Category:
JDBC

Cause:
When closing a prepared statement in the prepared statement cache for the specified data source connection pool, an error occurred.

Action:
Check the associated error that is printed and, if possible, correct the problem.

BEA-001132
Initialized statement cache of size "{1}" for connection in pool "{0}".

Category:
JDBC

Cause:
A prepared statement cache has been enabled for a connection in the specified data source connection pool.

Action:
No action is required. If you do not want statement caching turned on for the pool, do not configure or disable it.

BEA-001133
Statement caching is not enabled for connection in specified data source connection pool "{0}".

Category:
JDBC

Cause:
A configured data source connection pool has been started without statement caching being enabled.

Action:
No action is required. If you want statement caching turned on for the pool, configure and enable it.

BEA-001134
Statement caches of connections in the data source connection pool "{0}" have been cleared by "{1}".

Category:
JDBC

Cause:
The statement caches for connections in the specified data source connection pool have been cleared, as requested by the application.

Action:
No action is required.

BEA-001135
Initializing the JDBC service.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001136
Initialization failed.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001137
Initialization complete.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001138
Resuming the JDBC service.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001139
Resume failed.

Category:
JDBC

Cause:
Check earlier messages that are printed in the log.

Action:
No action is required.

BEA-001140
Resume complete.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001141
Suspending the JDBC service.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001142
Suspend of JDBC service failed.

Category:
JDBC

Cause:
Check earlier messages that are printed in the log.

Action:
No action is required.

BEA-001143
Suspend completed.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001144
Force Suspending the JDBC service.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001145
Force suspend of the JDBC service failed.

Category:
JDBC

Cause:
Check earlier messages that are printed in the log.

Action:
No action is required.

BEA-001146
Force suspend of the JDBC service completed.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001147
Shutting down the JDBC service.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001148
Shutdown of the JDBC service failed.

Category:
JDBC

Cause:
Check earlier messages that are printed in the log.

Action:
No action is required.

BEA-001149
Shutdown of the JDBC service has completed.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001150
Connection pool "{0}" deployment failed with the following error: {1}.

Category:
JDBC

Cause:
The cause should be indicated in the exception message.

Action:
Correct the problem described in the exception message.

BEA-001151
Data source "{0}" deployment failed with the following error: {1}.

Category:
JDBC

Cause:
The cause should be indicated in the exception message.

Action:
Correct the problem described in the exception message.

BEA-001152
Cannot enable statement caching for connection in pool "{0}", because it is using the WebLogic Type-2 XA driver.

Category:
JDBC

Cause:
Statement caching has been disabled for the specified data source connection pool because the connection pool is using the WebLogic Type-2 XA driver. This driver has a limitation based on the implementation using the ORACLE OCI interface. Cursors are closed when XAResource.end is called, causing all prepared statements to no longer be valid.

Action:
No action is required. Use a different driver if you want to use the prepared statement cache with the driver.

BEA-001154
Disabling statement caching for connection in pool "{0}".

Category:
JDBC

Cause:
Statement caching has been disabled for the specified data source connection pool for one or more reasons. 1. The size is explicitly configured to 0. 2. The Oracle replay driver is being used. 3. The Oracle statement cache is enabled.

Action:
No action required.

BEA-001155
The following exception has occurred:

Category:
JDBC

Cause:
An error condition has occurred.

Action:
Look for the associated exception in the log or your program to see what the results are. In general, this stack trace will help with debugging an existing problem.

BEA-001156
Stack trace associated with message {0} follows:

Category:
JDBC

Cause:
An error condition was reported.

Action:
No action is required.

BEA-001157
Data source connection pool "{0}" being suspended by user "{1}".

Category:
JDBC

Cause:
The specified data source connection pool is being suspended, as requested by the application.

Action:
No action is required.

BEA-001158
Data source connection pool "{0}" being forcibly suspended by user "{1}".

Category:
JDBC

Cause:
The specified data source connection pool is being forcibly suspended, as requested by the application.

Action:
No action is required.

BEA-001159
Data source connection pool "{0}" is being resumed by user "{1}".

Category:
JDBC

Cause:
The specified data source connection pool is being resumed, as requested by the application.

Action:
No action is required.

BEA-001160
Data source connection pool "{0}" being forcibly destroyed by user "{1}"

Category:
JDBC

Cause:
The specified data source connection pool is being forcibly destroyed, as requested by the application.

Action:
No action is required.

BEA-001161
Data source connection pool "{0}" being destroyed by user "{1}".

Category:
JDBC

Cause:
The specified data source connection pool is being destroyed, as requested by the application.

Action:
No action is required.

BEA-001162
Data source connection pool "{0}" being forcibly shutdown by user "{1}".

Category:
JDBC

Cause:
The specified data source connection pool is being forcibly shutdown, as requested by the application.

Action:
No action is required.

BEA-001163
Data source connection pool "{0}" being shut down by user "{1}".

Category:
JDBC

Cause:
The specified data source connection pool is being shut down, as requested by the application.

Action:
No action is required.

BEA-001164
Unable to initialize connection in pool "{0}". Initialization SQL = "{1}". Received exception: "{2}".

Category:
JDBC

Cause:
The exception message should contain a reason for the failure.

Action:
Take appropriate corrective action.

BEA-001165
Invalid statment cache size "{1}" specified for connection in pool "{0}".

Category:
JDBC

Cause:
An invalid value has been specified for statement cache size for connections in the indicated data source connection pool.

Action:
Check the allowed limits for statement cache size for this data source connection pool and fix the specified value.

BEA-001166
Activation of application-scoped data source connection pool "{1}":"{2}":"{0}" failed. Received exception: "{3}".

Category:
JDBC

Cause:
The error message should contain the reason for the failure.

Action:
Take appropriate corrective action.

BEA-001167
Deactivation of application-scoped pool "{1}":"{2}":"{0}" failed. Received exception: "{3}".

Category:
JDBC

Cause:
The error message should contain the reason for the failure.

Action:
Take appropriate corrective action.

BEA-001168
Attempt to resume JDBCService when it is already running...Ignoring.

Category:
JDBC

Cause:
The application attempted to resume JDBCService, although the service is already running.

Action:
Take appropriate corrective action.

BEA-001169
Error occured during shutdown of pool "{0}". Received exception: "{1}".

Category:
JDBC

Cause:
The exception should contain the reason for the failure.

Action:
Take appropriate corrective action.

BEA-001170
Unable to initialize JDBC Log. Received exception: "{0}".

Category:
JDBC

Cause:
The message should contain the reason for the failure.

Action:
Take appropriate corrective action.

BEA-001171
Unable to close connection "{0}". Received exception: "{1}".

Category:
JDBC

Cause:
The message should contain the reason for the failure.

Action:
Take suitable action if possible. Otherwise, contact My Oracle Support.

BEA-001172
Error occurred during shutdown of data source "{0}". Received exception: "{1}".

Category:
JDBC

Cause:
The message should contain the reason for the failure.

Action:
Take appropriate corrective action.

BEA-001173
"TestTableName" attribute for pool "{0}" being dynamically changed to "{1}".

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001174
Creating data source named {0}, JNDI Name = {1}.

Category:
JDBC

Cause:
The user requested that the data source be created, either implicitly or explicitly.

Action:
No action is required.

BEA-001175
Creating transactional data source named {0} for Pool {1}.

Category:
JDBC

Cause:
The user requested that the transactional data source be created, either implicitly or explicitly.

Action:
No action is required.

BEA-001176
Creating multi data source named {0}.

Category:
JDBC

Cause:
The user requested that the multi data source be created, either implicitly or explicitly.

Action:
No action is required.

BEA-001177
Creating data source connection pool named {0}, URL = {1}, Properties = {2}.

Category:
JDBC

Cause:
A request was issued to create the data source connection pool, either implicitly or explicitly.

Action:
No action is required.

BEA-001178
Attempt to set query timeout on a statement failed : {0}.

Category:
JDBC

Cause:
The reported message should contain a description of the failure.

Action:
Contact My Oracle Support.

BEA-001250
Unable to load application configured callback {1} for multi data source {0}, got error: {2}. Application control of multi data source failover behaviour will not work.

Category:
JDBC

Cause:
This is most likely because the application-defined class location has not been added to the CLASSPATH environment varible.

Action:
Please check that you specified the correct class name and that your CLASSPATH includes this class.

BEA-001251
Application configured callback {1} for multi data source {0} does not implement required interface {2}. Application control of multi data source failover behaviour will not work.

Category:
JDBC

Cause:
The configured callback {1} does not implement the required interface {2}.

Action:
Refer to the WebLogic Server documentation.

BEA-001252
Unable to add notification listener for Config MBean for multi data source {0} failed, got exception: {1}.

Category:
JDBC

Cause:
The reported exception should indicate the cause of the failure.

Action:
Refer to the WebLogic Server documentation.

BEA-001254
Multi data source {0} unable to disable connection pool {1}, got exception: {2}.

Category:
JDBC

Cause:
The reported exception should indicate the cause of the failure.

Action:
Refer to the WebLogic Server documentation.

BEA-001255
Multi data source {0} unable to disable connection pool {1}, got exception: {2}.

Category:
JDBC

Cause:
The reported exception should indicate the cause of the failure.

Action:
Refer to the WebLogic Server documentation.

BEA-001256
Dynamically changing the value of attribute FailoverRequestIfBusy for multi data source {0} from {1} to {2}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001257
Dynamically changing value of attribute HealthCheckFrequencySeconds for multi data source {0} from {1} to {2}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001258
Unable to setup timer for multi data source {0}, got exception: {1}.

Category:
JDBC

Cause:
The reported exception should indicate the cause of the failure.

Action:
Refer to the WebLogic Server documentation.

BEA-001259
Application has disallowed multi data source {0} from re-enabling data source connection pool {1}, which had previously been found dead and was disabled.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001260
Multi data source {0} unable to enable connection pool {1}, got exception: {2}.

Category:
JDBC

Cause:
The reported exception should indicate the cause of the failure.

Action:
Refer to the WebLogic Server documentation.

BEA-001261
Multi data source {0} unable to enable connection pool {1}, got exception: {2}.

Category:
JDBC

Cause:
The reported exception should indicate the cause of the failure.

Action:
Refer to the WebLogic Server documentation.

BEA-001262
Registered application callback {1} for multi data source {0} to control multi data source failover behavior.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001500
Creating application-coped multi data source {0}, algorithm type {3} for Application {1}, Module {2}.

Category:
JDBC

Cause:
The user requested that the multi data source be created, either implicitly or explicitly.

Action:
No action is required.

BEA-001501
Creating multi data source {0}, algorithm type {1}.

Category:
JDBC

Cause:
A request was made to create the multi data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001503
Creating application-scoped data source connection pool {0} for Application {1}, Module {2}, URL = {3}, Properties = {4}.

Category:
JDBC

Cause:
A request was made to create the data source connection pool, either implicitly or explicitly.

Action:
No action is required.

BEA-001504
Destroying multi data source {0}, created for Application {1}, Module {2}.

Category:
JDBC

Cause:
A request was made to destroy the multi data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001505
Destroying multi data source Pool {0}.

Category:
JDBC

Cause:
A request was made to destroy the multi data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001507
Destroying data source connection pool {0}, created for Application {1}, Module {2}.

Category:
JDBC

Cause:
A request was made to destroy the data source connection pool, either implicitly or explicitly.

Action:
No action is required.

BEA-001508
Destroying data source connection pool {0}.

Category:
JDBC

Cause:
A request was made to destroy the data source connection pool, either implicitly or explicitly.

Action:
No action is required.

BEA-001510
Creating application-scoped data source {0} for Application {1}, Module {2}, Application Context Name = {3}.

Category:
JDBC

Cause:
A request was made to create the data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001512
Data source {0} has been successfully created.

Category:
JDBC

Cause:
A request was made to create the data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001513
Destroying application-scoped data source {0}, created for Application {1}, Module {2}.

Category:
JDBC

Cause:
A request was made to destroy the data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001514
Destroying data source {0}.

Category:
JDBC

Cause:
A request was made to destroy the data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001515
Data source {0} has been successfully destroyed.

Category:
JDBC

Cause:
A request was made to destroy the data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001516
Data source connection pool "{0}" connected to Database: "{1}", Version: "{2}".

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001517
Data source connection pool "{0}" using Driver: "{1}", Version: "{2}".

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001518
Data source connection pool "{0}" Connection Usage Data:

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001519
Id : "{0}"

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001520
Timestamp : "{0}"

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001521
User : "{0}"

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001522
Data source connection pool "{0}" Connection Wait Data:

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001523
Data source connection pool "{0}" Connection Leak Data:

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001524
Data source connection pool "{0}" Connection Reserve Fail Data:

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001525
Data source connection pool "{0}" Statement Cache Entry Data:

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001526
Unable to load class "{0}", got exception : {1}. Driver Interception feature disabled.

Category:
JDBC

Cause:
This is most likely because the application-defined class' location has not been added to the CLASSPATH environment varible.

Action:
Please check that you specified the correct class name and that your CLASSPATH includes this class.

BEA-001527
Application configured class {0} does not implement required interface {1}. Driver Interception feature disabled.

Category:
JDBC

Cause:
The configured class {0} does not implement the required interface {1}.

Action:
Refer to the WebLogic Server documentation.

BEA-001528
Driver Interceptor class {0} loaded.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001529
JDBC loggging last resource (LLR) connection pool {0} did not find its table and is creating a new one using the following SQL: {1}

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001530
JDBC loggging last resource (LLR) connection pool {0} retrieved {1} record(s) from the database table {2}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001531
Received updated event for unexpected type of bean: {0}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001532
Data source connection pool "{0}" Statement Usage Data:

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001533
Pool Name : "{0}"

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001534
Data source connection pool "{0}" Connection Last Usage Data:

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001535
Data source connection pool "{0}" Connection Multi-threaded Usage Data:

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001536
Creating multi data source named {0}, JNDI Name = {1}.

Category:
JDBC

Cause:
A request was made to create the multi data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001537
Creating application-scoped multi data source {0} for Application {1}, Module {2}, Application Context Name = {3}.

Category:
JDBC

Cause:
A request was made to create the multi data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001538
Created multi data source named {0}.

Category:
JDBC

Cause:
A request was made to create the multi data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001539
Destroying multi data source {0}.

Category:
JDBC

Cause:
A request was made to destroy the multi data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001540
Destroying application-scoped multi data source {0}, created for Application {1}, Module {2}.

Category:
JDBC

Cause:
A request was made to destroy the multi data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001541
Destroyed multi data source named {0}.

Category:
JDBC

Cause:
A request was made to destroy the multi data source, either implicitly or explicitly.

Action:
No action is required.

BEA-001542
JVM DriverManager Login Timeout value set to {0}.

Category:
JDBC

Cause:
The application has specified this behavior to be enabled, via the corresponding configuration setting.

Action:
No action is required.

BEA-001543
Received change event: {1} for unexpected type of bean: {0}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001544
Received add event: {1} for unexpected type of bean: {0}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001545
Received unexpected event: {1} for unexpected type of bean: {0}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001546
Data source connection pool "{0}" is being started by user "{1}".

Category:
JDBC

Cause:
The specified data source connection pool is being started, as requested by the administrator.

Action:
No action is required.

BEA-001547
The "{0}" field value "{1}" in table reference "{2}" format [[[catalog.]schema.]table) is too long. The database supports a maximum length of "{3}" for this field.

Category:
JDBC

Cause:
This is a configuration error.

Action:
When configuring a table name, choose a shorter name for the indicated field. Note that JDBC stores automatically append "WLStore" to the table name.

BEA-001548
Empty field value in table reference "{0}" (format [[[catalog.]schema.]table).

Category:
JDBC

Cause:
This is a configuration error.

Action:
Ensure that the entire table reference is blank, or that the table field is not blank. If there is no schema, ensure that there are no periods "." in the table reference. Do not start the table reference with a period ".". Note that JDBC stores automatically append "WLStore" to table references.

BEA-001549
An old style WebLogic driver URL {0} is used. Because the WebLogic driver URL auto-convert switch is turned on, it is converted to {1}.

Category:
JDBC

Cause:
An old style WebLogic driver URL is used and the WebLogic driver URL auto-convert switch is turned on.

Action:
No action is required.

BEA-001550
WebLogic Oracle driver is being used. The driver URL is {0}. WebLogic Server no longer supports the WebLogic Oracle driver.

Category:
JDBC

Cause:
The WebLogic Oracle driver has been deprecated and removed.

Action:
Stop using the WebLogic Oracle driver, use the Oracle Thin driver instead.

BEA-001551
Application context for member data source {1} not found for standalone multi data source module {0}. Ensure that multi data source standalone modules have a higher deployment order than member data source standalone modules.

Category:
JDBC

Cause:
The deployment order of the multi data source is the same or lower than one of its member data sources.

Action:
Change the deployment order of the standalone multi data source to be greater than each member data source's deployment order.

BEA-001552
The logging last resource (LLR) data source {0} will not function when it is a participant in a global transaction that spans multiple WebLogic Server instances because remote JDBC support is disabled. LLR will function in single-server configurations.

Category:
JDBC

Cause:
Remote JDBC access over RMI is disabled.

Action:
Either configure the data source to use an XA-capable driver, or enable remote JDBC on all servers.

BEA-001553
Unable to deploy JDBC data source {0}. No credential mapper entry found for password indirection user {1}

Category:
JDBC

Cause:
No credential mapper entry was found for user {1} on data source {0}

Action:
Ensure that a credential mapper entry is defined for the data source {0} that maps the specified user name {1} to a password. The WebLogic Server administration console provides support for managing data source credential mapper entries.

BEA-001554
Data source connection pool "{0}" Connection Unwrap Data:

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001555
Invalid member data source {1} specified for multi data source {0}. GridLink data source may not be used in multi data source configurations.

Category:
JDBC

Cause:
A GridLink data source was specified as a multi data source member.

Action:
Either use a single GridLink data source or define generic data sources for use in a multi data source configuration.

BEA-001556
Data source {0} for service {1} registering with ONS daemons using configuration string {2}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001557
Data source {0} for service {1} unregistering with ONS daemons {2}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001558
Data source {0} for service {1} received a service down event for instance {2}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001559
Data source {0} for service {1} received a node down event for node {2}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001560
Data source {0} for service {1} received a service up event for instance {2}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001561
Data source {0} for service {1} received a node up event for node {2}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001562
Data source {0} for service {1} not registering for Fast Application Notification (FAN) events.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001563
ADM_DDL LLR (logging last resource) connection pool {0} did not find its table {1}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001564
JTSLoggableResourceTable.existsForADMDDL about to return: return value = {0}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001565
Logging last resource (LLR) data source {0} using LLR table {1} defined by system property weblogic.llr.table.{0}

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001566
JTSLoggableResourceTable.init for ADMDDL is generating SQL statement(createSQL): {0}.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001567
SQLRuntimeException caught at existsForADMDDL for poolName: {0} ddlName: {1} by: {2}.

Category:
JDBC

Cause:
Look at the printed exception to see why the call failed.

Action:
Correct the problem and run the operation again.

BEA-001568
Data source {0} for service {1} received a service up event

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001569
Data source {0} failed to create runtime MBean for RAC instance {1}. Exception={2}

Category:
JDBC

Cause:
Refer to the exception error message for the cause of the failure.

Action:
Try redeploying the data source or restart the WebLogic Server instance.

BEA-001570
Attempt to enable Fast Application Notification (FAN) support for a non-GridLink data source {0}, which is not supported.

Category:
JDBC

Cause:
Subscribing to FAN events is only supported by GridLink data sources.

Action:
Either set the FAN enabled attribute to false or configure a GridLink data source.

BEA-001571
Unable to load the connection labeling callback class "{0}", got exception : {1}.

Category:
JDBC

Cause:
This is most likely because the application-defined class' location has not been added to the CLASSPATH environment varible.

Action:
Please check that you specified the correct class name and that your CLASSPATH includes this class.

BEA-001572
Application-configured connection labeling callback class {0} does not implement required interface {1}.

Category:
JDBC

Cause:
The configured class {0} does not implement the required interface {1}.

Action:
Refer to the WebLogic Server documentation.

BEA-001573
Connection labeling callback class {0} loaded.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001574
Unable to load the connection Initialization callback class "{0}", got exception : {1}.

Category:
JDBC

Cause:
This is most likely because the application-defined class' location has not been added to the CLASSPATH environment varible.

Action:
Please check that you specified the correct class name and that your CLASSPATH includes this class.

BEA-001575
Application configured connection initialization callback class {0} does not implement required interface {1}.

Category:
JDBC

Cause:
The configured class {0} does not implement the required interface {1}.

Action:
Refer to the WebLogic Server documentation.

BEA-001576
Connection Initialization callback class {0} loaded.

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001580
An exception was thrown from the ConnectionHarvestingCallback: {0}.

Category:
JDBC

Cause:
The application callback threw an exception when the callback was called.

Action:
Look at the associated message. If more information is desired, turn on connection debuggging.

BEA-001581
An invalid scope of Application instead of Global is specified for data source {0}, URI = {1}.

Category:
JDBC

Cause:
The configuration is invalid. The specified data source must have a Global scope.

Action:
Correct the configuration for the specified data source.

BEA-001582
oracle.jdbc.DRCPConnectionClass must be specified if and only if a Database Resident Connection Pooling (DRCP) pool is defined.

Category:
JDBC

Cause:
The configuration is invalid.

Action:
Correct the configuration for the specified data source.

BEA-001583
The WebLogic statement cache size is disabled because Oracle statement cache is configured.

Category:
JDBC

Cause:
The WebLogic statement cache is disabled.

Action:
No action is required.

BEA-001584
Data source connection pool "{0}" disabled by multi data source "{1}".

Category:
JDBC

Cause:
The specified data source connection pool has been disabled by a multi data source.

Action:
No action is required.

BEA-001585
Data source connection pool "{0}" re-enabled by multi data source "{1}".

Category:
JDBC

Cause:
The specified data source connection pool has been re-enabled by a multi data source.

Action:
No action is required.

BEA-001586
EndRequest failed: {0}

Category:
JDBC

Cause:
This generally happens because the application failed to complete a local transaction before closing the connection. See the associated message to determine if this is the case.

Action:
The error is ignored if the connection can be cleared. This is, however, an application error to not complete the transaction. Fix the software.

BEA-001587
For LLR RAC DataSource {0} Member of MultiDataSource, test-on-reserve is disabled, and the health of the DataSource cannot be verified.

Category:
JDBC

Cause:
test-on-reserve is disabled in the data source configuration.

Action:
Enable test-on-reserve in the data source configuration. If all member data sources are marked as unhealthy and the WLS Administration Server fails to boot, use WLST to change the configuration.

BEA-001588
Shrinking connection pools due to memory pressure level of {0} exceeding shrink threshold of {1}.

Category:
JDBC

Cause:
There is increased memory consumption in the server.

Action:
No action is required.

BEA-001589
Setting all data source statement cache sizes to {0}% of configured sizes due to memory pressure level of {1}.

Category:
JDBC

Cause:
There is increased memory consumption in the server.

Action:
No action is required.

BEA-001590
Setting {0} statement cache size to {1} ({2}% of configured size {3}).

Category:
JDBC

Cause:
There is increased memory consumption in the server.

Action:
No action is required.

BEA-001591
Configuring data source {0} for partition {1}: {2}.

Category:
JDBC

Cause:
See the message body.

Action:
No action required.

BEA-001592
Forcibly releasing inactive connection "{1}" back into the data source connection pool "{0}".

Category:
JDBC

Cause:
The connection was found to be unused by the application for the specified duration (configured using InactiveConnectionTimeoutSeconds attribute of the pool MBean), and therefore is being forcibly released back into the pool.

Action:
Check the application code for leakages of connection objects, or tune the configured value of the specified connection pool attribute.

BEA-001593
Forcibly releasing harvested connection "{1}" back into the data source connection pool "{0}".

Category:
JDBC

Cause:
The connection was harvested and the application callback did not close the connection. This occurs only when Connection Leak Profiling is enabled.

Action:
Close the connection in the ConnectionHarvestingCallback.cleanup() method.

BEA-001594
Forcibly releasing an already closed connection "{1}" back into the data source connection pool "{0}".

Category:
JDBC

Cause:
When isClosed() is called on the connection, either directly by the application or when accessing a connection, the driver indicates that the connection is already closed. The connection is closed in the WLS data source and returned to the pool. The connection will be replaced in the pool with a new connection.

Action:
No action is required.

BEA-001595
Forcibly releasing connection "{1}" back into the data source connection pool "{0}" because of an initialization failure.

Category:
JDBC

Cause:
A failure occurred on the connection during initialization. The connection will be removed from the pool if it continues to have problems.

Action:
This may indicate a problem with the database. Review other errors in the WLS data source or the database logs.

BEA-001596
Data source connection pool "{0}" Connection Local Transaction Leak Data:

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001597
Data source connection pool "{0}" Closed JDBC Object Usage Data:

Category:
JDBC

Cause:
This is an informational message.

Action:
No action is required.

BEA-001598
Oracle Notification Service (ONS) initialization failed for data source {0}. ONS events will not be processed.

Category:
JDBC

Cause:
The ONS host and pair list is invalid or was unavailable for connection.

Action:
Check the ONS configuration to make sure that it is correct and available.

BEA-001599
When creating Active GridLink (AGL) data source named {0}, the URL should be the long format with a SERVICE_NAME.

Category:
JDBC

Cause:
An incorrect URL is specified for an AGL data source.

Action:
Correct the URL specified for the AGL data source.

BEA-001600
An error occurred while repurposing connection for pool {0}: {1}

Category:
JDBC

Cause:
Refer to the exception message for information about the condition that caused the error.

Action:
Correct the condition that led to the error.

BEA-002001
Received an unknown message type.

Category:
IIOP

Cause:
This should not occur. This indicates that the client is sending garbaged messages. It might also indicate that malicious third parties are trying to access the server using IIOP.

Action:
Contact My Oracle Support.

BEA-002002
Failed to parse method name {0}.

Category:
IIOP

Cause:
This can happen for a variety of reasons. Normally, it is because the caller made a request for a non-existent method. Alternatively, the IDL mangling of the method name may be ambiguous, so WebLogic Server cannot decide which method to call.

Action:
If the IDL mangling is causing a problem, try changing the name of the method. In particular, names such as getSomedata() (where somedata is also the name of an attribute or method) can cause problems. Also, some bugs with name mangling exist in JDK 1.3.1. Try using a JDK 1.4 client.

BEA-002003
Unable to send the message: {0}.

Category:
IIOP

Cause:
Some sort of communication failure has occurred. This could be because the target closed the IIOP connection or because of some transient network fault.

Action:
Verify that the client-server network connection is working.

BEA-002005
OutOfMemoryError in adapter: {0}.

Category:
IIOP

Cause:
This is often caused by marshalling mismatches between the client and the server and is generally a bug in either the client or the server or both.

Action:
Restart the server and contact My Oracle Support.

BEA-002006
Cannot scavenge idle connections, {0}

Category:
IIOP

Cause:
The server was unable to schedule a trigger to watch for idle IIOP connections. The fact that it was unable to do so indicates some core failure in the server.

Action:
Restart the server. If this occurs again, contact Oracle Customer Support.

BEA-002008
Failed to export {0}. The following exception occurred: {1}.

Category:
IIOP

Cause:
This is most often caused by the server being unable to find or generate an IIOP stub for the remote object. Ensure that the Common Object Request Broker API (CORBA) objects have corresponding _Stub classes in the server classpath. RMI-IIOP object stubs should be generated automatically.

Action:
For CORBA objects, ensure that the idlj was run on the server class. For RMI-IIOP objects, contact My Oracle Support.

BEA-002011
Failed to marshal exception {0}: {1}.

Category:
IIOP

Cause:
The server could not find the appropriate exception definitions in its classpath. For Common Object Request Broker API (CORBA) exceptions, the application must contain the exception helper classes as well as the exception classes.

Action:
Add missing exception classes to the application.

BEA-002012
Failed to send exception {0}: {1}.

Category:
IIOP

Cause:
This only happens if the connection between the client and server was very unreliable.

Action:
Verify that the client-server network connection is working. Contact My Oracle Support.

BEA-002013
Complete failure to send exception {0}: {1}.

Category:
IIOP

Cause:
Some sort of communication failure has occurred. This could be because the target closed the IIOP connection or because of some transient network fault.

Action:
Verify the client-server network connection.

BEA-002014
IIOP subsystem enabled.

Category:
IIOP

Cause:
The IIOP subsystem is operational and is listening for incoming IIOP requests.

Action:
No action is required.

BEA-002015
Using javax.rmi.CORBA.UtilClass {0}; The IIOP subsystem requires a WebLogic Server-compatible UtilClass.

Category:
IIOP

Cause:
Some application code, or a foreign object request broker (ORB), set the system property javax.rmi.CORBA.UtilClass or tried accessing javax.rmi.CORBA.Util functions before the IIOP subsystem had initialized.

Action:
The IIOP subsystem will not function correctly in this scenario. Correct the application code and restart the server.

BEA-002016
Using javax.rmi.CORBA.PortableRemoteObjectClass {0}, the IIOP subsystem requires a WebLogic Server-compatible PortableRemoteObjectClass.

Category:
IIOP

Cause:
Some application code, or a foreign object request broker (ORB), set the system property javax.rmi.CORBA.PortableRemoteObjectClass or tried accessing javax.rmi.PortableRemoteObject functions before the IIOP subsystem had initialized.

Action:
The IIOP subsystem will not function correctly in this scenario. Correct the application code and restart the server.

BEA-002017
LocateRequest is {0}.

Category:
IIOP

Cause:
This is an informational message.

Action:
No action is required.

BEA-002018
Default GIOP version is 1.{0}

Category:
IIOP

Cause:
This is an informational message.

Action:
No action is required.

BEA-002019
LocationForward policy is {0}.

Category:
IIOP

Cause:
This is an informational message.

Action:
No action is required.

BEA-002021
SecurityService registered under {0}.

Category:
IIOP

Cause:
This is an informational message.

Action:
No action is required.

BEA-002022
Could not bind SecurityService {0}.

Category:
IIOP

Cause:
This is an internal JNDI problem.

Action:
Contact My Oracle Support.

BEA-002023
Could not resolve SendingContext RunTime: {0}.

Category:
IIOP

Cause:
An invalid object reference for SendingContext RunTime was provided by the client.

Action:
Contact My Oracle Support.

BEA-002026
Transaction mechanism is {0}.

Category:
IIOP

Cause:
This is an informational message.

Action:
No action is required.

BEA-002027
Complete failure to rewrite exception from {0}: {1}.

Category:
IIOP

Cause:
This error should not occur.

Action:
Contact My Oracle Support.

BEA-002028
An OTS error occurred: {0}, {1}.

Category:
IIOP

Cause:
OTS errors are generally not bugs but always result in exception information being lost when propagated to the caller. Thus, the root cause is always logged, so that system administrators can determine the real cause. OTS errors are generally caused by some transaction subsystem operation (for instance, a transaction being rolled back).

Action:
Ensure that this is an expected error.

BEA-002033
Codeset for {0} data set to {1}, OSF registry entry {2}.

Category:
IIOP

Cause:
This is an informational message.

Action:
No action is required.

BEA-002037
CosNaming Service registered under {0}.

Category:
IIOP

Cause:
This is an informational message.

Action:
No action is required.

BEA-002038
Could not bind the CosNaming Service {0}.

Category:
IIOP

Cause:
This is an internal JNDI problem.

Action:
Contact My Oracle Support.

BEA-002039
Replacer: {0}

Category:
IIOP

Cause:
The replacer did not have enough information to do a proper replacement.

Action:
Contact My Oracle Support.

BEA-002041
Connection attempt was rejected because IIOP is not enabled on this channel.

Category:
IIOP

Cause:
The connection attempt was rejected because IIOP is not enabled at all for this server, as determined by the ServerMBean, or is not enabled on this particular channel.

Action:
Enable IIOP.

BEA-002043
Naming exception: {0}

Category:
IIOP

Cause:
A standard exception was generated by the naming implementation.

Action:
No action is required.

BEA-002044
Class not found: class= {0}, repId={1}, codebase={2}

Category:
IIOP

Cause:
Class not found.

Action:
Add the required class to CLASSPATH.

BEA-002605
Adding address: {0} to the licensed client list.

Category:
Server

Cause:
The server accepted a connection from the specified client.

Action:
No action is required.

BEA-002606
The server is unable to create a server socket for listening on channel "{3}". The address {0} might be incorrect or another process is using port {1,number,0}: {2}

Category:
Server

Cause:
The address was incorrect or another process was using the port.

Action:
Use ipconfig or ifconfig to check if the listen address is valid, and use netstat to check that the specified port is not in use by another process.

BEA-002607
Channel "{2}", listening on {0}:{1,number,0}, was shut down.

Category:
Server

Cause:
The server or channel was shut down.

Action:
No action is required. If this was an unexpected error, contact My Oracle Support.

BEA-002608
The ListenThread failed because of an error: {0}

Category:
Server

Cause:
An exception occurred when the server socket was unable to accept client connections.

Action:
Check the file descriptor limit. Tune the operating system parameters that handle socket creation using ServerSocket.

BEA-002609
Channel Service initialized.

Category:
Server

Cause:
The Channel subsystem is operational.

Action:
No action is required.

BEA-002610
Dynamic Listener Service initialized.

Category:
Server

Cause:
The dynamic listener subsystem is operational.

Action:
No action is required.

BEA-002611
The hostname "{0}", maps to multiple IP addresses: {1}.

Category:
Server

Cause:
The host name of the server resolved to multiple IP addresses, which can cause problems for the Administration Server.

Action:
Check if this was done on purpose.

BEA-002612
Channel "{2}", listening on {0}:{1,number,0}, did not start did not start properly.

Category:
Server

Cause:
Some of the listen ports did not open or failed within the configured grace period.

Action:
Ensure that none of the configured listen ports are in use by other processes.

BEA-002613
Channel "{2}" is now listening on {0}:{1,number,0} for protocols {3}.

Category:
Server

Cause:
The server successfully started the listen thread and server socket.

Action:
No action is required.

BEA-002614
Reopening channel "{2}" on {0}:{1,number,0}.

Category:
Server

Cause:
The server backed off because a socket exception occurred while accepting client connections. The server is now ready to accept connections.

Action:
No action is required.

BEA-002615
After having failed to listen, the server is now listening on channel "{2}" on {0}:{1,number,0}.

Category:
Server

Cause:
The server backed off because a socket exception occurred while accepting client connections. The server is now ready to accept connections.

Action:
No action is required.

BEA-002616
Failed to listen on channel "{2}" on {0}:{1,number,0}, failure count: {3}, failing for {4} seconds, {5}

Category:
Server

Cause:
An exception occurred while trying to accept client connections. The server will try to back off to aid recovery.

Action:
The operating system (OS) limit for the number of open file descriptors (FD limit) needs to be increased. Tune the OS parameters that might help the server to accept more client connections (for example, TCP accept back log).

BEA-002617
Attempting to close and reopen the server socket on channel "{2}" on {0}:{1,number,0}.

Category:
Server

Cause:
The server listener could not accept a socket connection and failed after several simple retries. It has closed and reopened the server socket.

Action:
Check if the file decriptor limit needs to be increased. Tune the operating system parameters that might help the server accept more client connections.

BEA-002618
An invalid attempt was made to configure a channel for unconfigured protocol "{0}".

Category:
Server

Cause:
The server configuration specified a channel that uses a protocol that is not enabled.

Action:
Enable the protocol in the server configuration.

BEA-002619
One or more listen ports did not start properly.

Category:
Server

Cause:
One or more listen ports failed to open during server startup.

Action:
Ensure that none of the configured listen ports are in use by other processes.

BEA-002620
An invalid attempt was made to configure a channel for server "{0}" on an unknown listen address "{1}".

Category:
Server

Cause:
The server configuration specified a channel that uses a listen address that does not exist.

Action:
Correct the server configuration.

BEA-002621
The connection was rejected because the server license only allows connections from {0} unique IP addresses.

Category:
Server

Cause:
Clients tried to connect from more distinct addresses than the license allows.

Action:
Use a server license that allows for more clients to connect.

BEA-002622
The protocol "{0}" is now configured.

Category:
Server

Cause:
The server has loaded a protocol making it available for outbound traffic and configurable for inbound traffic.

Action:
No action is required.

BEA-002623
Connection rejected, the server is in the {0} state. Remote Server contacting us is {1}

Category:
Server

Cause:
Clients tried to connect to the server before it was in the RUNNING state.

Action:
Connect to the server after it has started.

BEA-002624
The administration protocol is "{0}" and is now configured.

Category:
Server

Cause:
The server has loaded the administration protocol making it available for outbound traffic and configurable for inbound traffic.

Action:
No action is required.

BEA-002625
An attempt to configure channel "{0}" failed because of {1}.

Category:
Server

Cause:
The cause is detailed in the accompanying exception.

Action:
Review the exception.

BEA-002626
The protocol "{0}" could not be loaded: {1}

Category:
Server

Cause:
Consult the exception for why the protocol could not be loaded.

Action:
Consult the exception for why the protocol could not be loaded.

BEA-002627
The domain configuration must have at least one administration channel on every server or no administration channels at all.

Category:
Server

Cause:
The server was contacted by a server that did not reflect the same administration state as itself.

Action:
Modify the domain configuration so that all servers have administration channels, or enable the domain-wide administration port.

BEA-002628
Unable to export RemoteLifeCycleOperations RMI object due to {0}.

Category:
Server

Cause:
The RMI export failed.

Action:
Contact My Oracle Support and provide the logs.

BEA-002630
Accepting connections again.

Category:
Server

Cause:
The server is accepting client connections again after refusing connections as part of server throttling.

Action:
No action is required.

BEA-002631
Max threshold reached for open sockets [total open sockets: {0}, allowed max: {1}]. No more connections allowed.

Category:
Server

Cause:
The MaxOpenSocketCount attribute of the server configuration defines the upper bound of the number of open sockets.

Action:
Increase the MaxOpenSocketCount attribute of the server configuration. Use the server tuning tab in the Administration Console.

BEA-002632
Found jrmp.jar in {0} directory. JRMP service is now enabled.

Category:
Server

Cause:
JRMP is enabled.

Action:
No action is required.

BEA-002633
A port conflict was detected in the server "{4}" configuration. The server "{4}" is configured to listen on two ports that have the same port number and IP address. Channel "{0}" address "{1}" conflicts with channel "{2}" address "{3}".

Category:
Server

Cause:
The server is configured to listen on two ports that have the same port number and IP address.

Action:
Ensure that the address identities [ListenAddress and ListenPort combinations] are distinct and unique.

BEA-002634
The server "{0}" disconnected from this server.

Category:
Server

Cause:
The remote server may have crashed, been shut down normally or been partitioned from the network.

Action:
No action is required.

BEA-002635
The server "{0}" connected to this server.

Category:
Server

Cause:
The remote server may have been booted or a network partition may have been resolved.

Action:
No action is required.

BEA-002636
Unable to update server "{0}" with local channel information.

Category:
Server

Cause:
The remote server may have crashed, been shut down normally or been partitioned from the network.

Action:
No action is required.

BEA-002637
Failed to register a disconnect listener because of {0}

Category:
Server

Cause:
This can happen during server startup when the incoming network connection is not suitable for callbacks and the booting server does not yet have a listen port open.

Action:
No action is required. The server should eventually be connected properly.

BEA-002638
{0} was issued remotely from {1}.

Category:
Server

Cause:
Log the host address of the machine that issued the SLC operation.

Action:
No action is required.

BEA-002639
ServerRuntime:{0}

Category:
Server

Cause:
This is an informational message.

Action:
No action is required.

BEA-002640
A request has been received to force a shutdown of the server.

Category:
Server

Cause:
This is an informational message.

Action:
No action is required.

BEA-002641
-DserverType is set to an unrecognized value: {0}. The server will start with all services enabled.

Category:
Server

Cause:
An undefined server type was specified or a typographical error was made.

Action:
See the WebLogic Server documentation for valid values for -DserverType.

BEA-002642
{0} not found. The server will start with all services enabled.

Category:
Server

Cause:
The file was deleted or moved.

Action:
Replace the file from the WebLogic Server installation.

BEA-002643
Attempt to read {0}, failed: {1}

Category:
Server

Cause:
The file has been corrupted or had its permissions changed.

Action:
Replace the file with one from the WebLogic Server installation.

BEA-002644
The JAR file {0} being processed as a potential service plug-in could not be read: {1}

Category:
Server

Cause:
The file may be damaged.

Action:
Check the file, replace & and try again.

BEA-002645
The manifest of the JAR file {0} being processed as a potential service plug-in, could not be read: {1}

Category:
Server

Cause:
The manifest may be corrupted.

Action:
Replace the file and retry.

BEA-002646
Unable to load the service plug-in activator class from {0}: {1}

Category:
Server

Cause:
The plug-in JAR file does not meet the service plug-in requirements.

Action:
Check the contents of the JAR file and retry.

BEA-002647
The service plug-in, {1}, was added from {0}.

Category:
Server

Cause:
The plugin was placed in the domain lib directory.

Action:
No action is required. To remove the plug-in, remove it from the domain lib directory.

BEA-002648
Could not obtain the relevant ServerRuntimeMBean for server {0}.

Category:
Server

Cause:
The remote server runtime object for server {0} could not be obtained. This can happen if the server has already been shut down or is otherwise unavailable.

Action:
If the server is active when this error occurs, contact My Oracle Support.

BEA-002649
A port conflict was detected in the server "{3}" configuration. Both TCP and SDP channels are configured to listen on the same port number and IP address. Channels "{0}" and "{1}" on address "{2}".

Category:
Server

Cause:
Both TCP and SDP channels are configured to listen on the same port number and IP address.

Action:
Ensure that the channels with the same [ListenAddress and ListenPort combinations] either all support SDP or do not support SDP.

BEA-002650
Unable to schedule reconnection to a disconnected server.

Category:
Server

Cause:
The default timer manager has stopped. This is normal during server shutdown.

Action:
None required if the server is in the process of shutting down.

BEA-002651
The process for the server {0} has not completely shut down. This problem should be reported and you may have to kill the process manually.

Category:
Server

Cause:
The process for the server {0} has not completely shut down.

Action:
Kill the process manually.

BEA-002652
The server has no configured channels.

Category:
Server

Cause:
The server has no configured channels.

Action:
Create or define a correct channel configuration.

BEA-002653
The server''s administration channel conflicts with the Administration Server''s channel.

Category:
Server

Cause:
The server's administration channel conflicts with the Administration Server's channel.

Action:
Check the server channel configuration and fix the conflicts.

BEA-002654
Initialization Failed: {0}

Category:
Server

Cause:
Initialization Failed: {0}

Action:
Review the returned error and take appropriate action to fix it.

BEA-002655
Cannot dynamically create new channel with admin protocol on Managed server {0} while it is running.

Category:
Server

Cause:
An attempt was made to create a new channel with admin protocol on Managed server {0} while the server is running.

Action:
Shut down the Managed Server and then try creating the channel again.

BEA-002656
Cannot dynamically enable or disable adminstration port on Managed Server {0} while it is running.

Category:
Server

Cause:
An attempt was made to dynamically enable or disable the adminstration port on Managed Server {0} while the server is running.

Action:
Shut down the Managed Server and then try enabling or disabling the port again.

BEA-002657
Cannot change MaxOpenSockCount enablement dynamically on Managed Server {0} while it is running.

Category:
Server

Cause:
An attempt was made to dynamically change MaxOpenSockCount enablement on Managed Server {0} while the server is running.

Action:
Shut down the Managed Server and then try to change MaxOpenSockCount enablement again.

BEA-002658
No configured outbound channel for {0}.

Category:
Server

Cause:
No configured outbound channel for {0}.

Action:
Review the returned error and take appropriate action to fix it.

BEA-002659
Only local HostID is supported {0}.

Category:
Server

Cause:
Only the local HostID is supported {0}

Action:
Check and fix the error.

BEA-002660
Failed to parse replication ports for server {0} port range: {1}.

Category:
Server

Cause:
Parsing replication ports for server {0} port range: {1} failed.

Action:
Check and fix the error.

BEA-002661
Server failed to bind to any usable port.

Category:
Server

Cause:
The server failed to bind to any usable port.

Action:
See the preceding log message for details.

BEA-002662
Server was unable to verify whether {0} maps to multiple addresses due to {1}.

Category:
Server

Cause:
Review the contents of the included error message for the cause.

Action:
Review the contents of the included error message to determine the appropriate action to take.

BEA-002663
Uncaught Throwable in processSockets {0}.

Category:
Server

Cause:
An unhandled Throwable error occurred while processing sockets.

Action:
Check for other log messages that give more information about the failure.

BEA-002664
Failed to start Admin Channel {0}.

Category:
Server

Cause:
There was an error binding to the Admin Channel port. The port may already be in use.

Action:
Check for a port conflict.

BEA-002665
A partition "{0}" appears to use a server resource; channel: {1}.

Category:
Server

Cause:
The server channel is a shared resource and cannot belong to a partition.

Action:
Check whether this is not a Coherence partition. Otherwise configure either port-offset or explicit-port or uri-prefix.

BEA-002666
RemoteChannelService: {0} {1}

Category:
Server

Cause:
managed server failed to connect AdminServer due to this error.

Action:
Check exception message to resolve connection error.

BEA-002900
Initializing self-tuning thread pool.

Category:
WorkManager

Cause:
The server is starting.

Action:
No action is required.

BEA-002901
Creating Work Manager "{2}" with configured minimum threads constraint "{3}" and maximum threads constraint "{4}" for module "{0}" and application "{1}"

Category:
WorkManager

Cause:
The application is being initialized.

Action:
No action is required.

BEA-002902
Creating execute queue "{0}".

Category:
WorkManager

Cause:
The server is starting.

Action:
No action is required.

BEA-002903
Creating Work Manager from "{1}" WorkManagerMBean for application "{0}"

Category:
WorkManager

Cause:
The application is being initialized.

Action:
No action is required.

BEA-002908
Unable to create runtime MBean for Work Manager {0}. {1}

Category:
WorkManager

Cause:
A fatal error occurred while creating the runtime MBeans.

Action:
Contact My Oracle Support with the server logs.

BEA-002911
Work Manager {0} failed to schedule a request due to {1}

Category:
WorkManager

Cause:
Work Manager did not schedule a request due to a fatal failure.

Action:
This is a critical failure. Report to My Oracle Support with the logs.

BEA-002912
Overload Manager {0} rejected request as current length {1} exceeds max capacity of {2}

Category:
WorkManager

Cause:
A request was rejected as the overload capacity was reached or exceeded.

Action:
No action is required.

BEA-002913
Work Manager {0} rejected request as the server is low on memory

Category:
WorkManager

Cause:
A request was rejected as the server was low on memory.

Action:
No action is required.

BEA-002914
Shutdown callback invocation failed with: {0}

Category:
WorkManager

Cause:
There was an internal WebLogic Server error in the application shutdown.

Action:
Report to My Oracle Support with the logs.

BEA-002916
Request belonging to Work Manager {0}, application {1} is rejected as the WorkManager is shutdown.

Category:
WorkManager

Cause:
The request was refused entry because the Work Manager was shutdown.

Action:
No action is required.

BEA-002917
Enqueued request belonging to Work Manager {0}, application {1} is cancelled as the Work Manager is shutdown.

Category:
WorkManager

Cause:
The request was refused because the Work Manager was shutdown.

Action:
No action was required.

BEA-002918
Server detected execute queue(s) in self-tuning mode. Execute queues will not be self-tuned. They retain their behavior from earlier releases. Consider using Work Managers to take advantage of self-tuning.

Category:
WorkManager

Cause:
The execute queues were detected in the self-tuning server.

Action:
Consider removing the execute queues. The server automatically adjusts the thread pool size for optimal performance. Work Managers can be used to change the default behavior where needed.

BEA-002919
Unable to find a Work Manager with name {0}. Dispatch policy {0} will map to the default Work Manager for the application {1}

Category:
WorkManager

Cause:
There is no Work Manager with the given name.

Action:
This could indicate a configuration error. Check the dispatch-policy and ensure that it matches the name of a Work Manager defined either within the same application or globally.

BEA-002920
An instance of the mSA Work Manager

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002921
The name of the Work Manager

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002922
The number of waiting requests in the queue

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002923
The number of requests that have been processed

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002924
An instance of the MinThreadsConstraint for a particular Work Manager

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002925
Completed request count

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002926
Pending requests that are waiting for an available thread

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002927
Number of requests that are currently executing

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002928
Number of requests executed out of turn to satisfy this constraint

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002929
Number of requests that must be executed to satisfy the constraint

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002930
The maximum time a request had to wait for a thread. Only requests whose execution is needed to satisfy the constraint are considered.

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002931
Number of requests that must be executed to satisfy the constraint

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002932
An instance of the MaxThreadsConstraint for a particular Work Manager

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002933
Number of requests that are currently executing

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002934
Number of requests that are denied a thread for execution because the constraint is exceeded

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-002935
request-class-name reference within ContextCase element for entry {0} with value: {1} ;cannot be resolved for Work Manager.

Category:
WorkManager

Cause:
The request class specified in the context case is not defined.

Action:
Ensure that a request class with the same name as was specified in the context case request-class-name is configured.

BEA-002936
maximum thread constraint {0} is reached

Category:
WorkManager

Cause:
The number of threads assigned to this work manager has reached the configured value in the maximum threads constraint

Action:
No action is required.

BEA-002937
The maximum thread constraint {0} is no longer reached.

Category:
WorkManager

Cause:
The number of threads assigned to this Work Manager has dropped below the configured value in the maximum threads constraint.

Action:
No action is required.

BEA-002938
Global work manager "{0}" created with customized configuration

Category:
WorkManager

Cause:
The default configuration for a global work manager has been overriden and the work manager is created with a customized configuration

Action:
no action needed

BEA-002939
The maximum thread constraint {0} has been reached {1} times for the last {2} seconds.

Category:
WorkManager

Cause:
The number of threads assigned to this work manager has reached the configured value for the maximum threads constraint.

Action:
No action is required.

BEA-002940
Shutting down work manager "{0}" according to the configured work manager shutdown trigger.

Category:
WorkManager

Cause:
A work manager is being shut down because the number of stuck threads has reached the configured value in a work manager shutdown trigger.

Action:
Monitor the stuck threads to determine the reason why the requests have been taking a long time to process. If resumeWhenUnstuck is true, the work manager will be resumed when there are no more stuck threads for the work manager.

BEA-002941
Removed {0} threads from the standby thread pool.

Category:
WorkManager

Cause:
The server is reducing the number of threads in the standby thread pool either because they are not needed or to reduce overall resource usages of the server.

Action:
No action is required as the server auto tunes.

BEA-002942
CMM memory level becomes {0}. Setting standby thread pool size to {1}.

Category:
WorkManager

Cause:
CMM memory level has changed. Standby thread pool size may be adjusted accordingly.

Action:
No action is required.

BEA-002943
Maximum Threads Constraint "{0}" queue for work manager "{1}" reached maximum capacity of {2} elements. Consider setting a larger queue size for the maximum threads constraint.

Category:
WorkManager

Cause:
The max threads constraint queue is full.

Action:
Consider setting a larger queue size for the max threads constraint.

BEA-002944
Maximum Threads Constraint "{0}" queue for work manager "{1}" reached maximum capacity of {2} elements {3} times for the last {4} seconds. Consider setting a larger queue size for the maximum threads constraint.

Category:
WorkManager

Cause:
The max threads constraint queue is full.

Action:
Consider setting a larger queue size for the max threads constraint.

BEA-002945
Unable to perform ThreadLocal cleanup for self-tuning thread pool threads due to error: {0}

Category:
WorkManager

Cause:
Please see the error in the message for additional information.

Action:
Check the error in the message for details of the error and take approriate action if possible. It is also possible that ThreadLocal cleanup is not supported on your platform.

BEA-002946
Partition configuration for partition {0} is not available while loading work manager components for the partition.

Category:
WorkManager

Cause:
This message can be ignored if partition configuration is available at a later time. This could happen if the partition has just been created or if it has just been migrated from another server.

Action:
Check whether there is a log message WLS-002947 in the log file for the same partition. If not, verify if the partition is being created properly.

BEA-002947
Partition configuration for partition {0} is available. Work manager components for the partition have been loaded successfully.

Category:
WorkManager

Cause:
Partition configuration was not available earlier when trying to load work manager components for the partition. This message indicates that the partition configuration is now available and the work manager components have been loaded successfully.

Action:
No action is required. Earlier warning messages WLS-002946 and WLS-002948 for the same partition can now be disregarded.

BEA-002948
Error occurred while loading work manager components for partition {0}: {1}

Category:
WorkManager

Cause:
Please see the error in the message for additional information.

Action:
Check the error in the message for details of the error and take approriate action if possible.

BEA-002949
Work manager components configured for partition {0} is being accessed, but the partition is not deployed to this server.

Category:
WorkManager

Cause:
This can occur when there are possible inconsistencies in partition or resource group target configuration.

Action:
Check the partition or resource group targets configuration.

BEA-002950
Partition "{0}" is configured with a minimum threads constraint cap of {1}, which is less than the sum of all configured minimum threads constraints in the partition.

Category:
WorkManager

Cause:
The WebLogic administrator has set a cap on the number of threads that will be allocated to this partition for satifying its minimum threads constraints. The configured value is less than the sum of all configured minimum threads constraints configured in this partition.

Action:
Request a higher partition minimum threads constraint cap setting from the WebLogic administrator.

BEA-002951
An error occurred while trying to create a thread under the global context due to error: {0}. A thread wass created under the context of partition "{1}" instead.

Category:
WorkManager

Cause:
Check the error in the message for additional information about what might have caused the error.

Action:
Resource Consumption Management may not work properly with this error. Contact My Oracle Support and provide them with the logs.

BEA-002952
Partition maximum threads constraint for partition {0} has been reached.

Category:
WorkManager

Cause:
The number of threads assigned to this partition has reached the configured partition maximum threads constraint value.

Action:
No action is required.

BEA-002953
The partition maximum threads constraint for partition {0} has been reached {1} times in the last {2} seconds.

Category:
WorkManager

Cause:
The number of threads assigned to this partition has reached the configured partition maximum threads constraint value.

Action:
No action is required.

BEA-002954
The Partition Maximum Threads Constraint "{0}" queue reached maximum capacity of {2} elements when trying to add a work entry for work manager "{1}" to the queue. Consider setting a larger queue size for the partition maximum threads constraint.

Category:
WorkManager

Cause:
The partition maximum threads constraint queue is full.

Action:
Consider setting a larger queue size for the partition max threads constraint.

BEA-002955
The Partition Maximum Threads Constraint "{0}" reached maximum capacity of {2} elements {3} times in the last {4} seconds when trying to add work entries for work managers including "{1}". Consider setting a larger queue size for the partition maximum threads constraint.

Category:
WorkManager

Cause:
The partition maximum threads constraint queue is full.

Action:
Consider setting a larger queue size for the partition maximum threads constraint.

BEA-002956
The thread count tuning feature in the self-tuning thread pool has stopped due to {0}.

Category:
WorkManager

Cause:
The self-tuning timer task has to stop due to an unrecoverable error.

Action:
The self-tuning thread pool would continue to process work request, althought without further adjustment of the thread pool size. Consider restarting the server if the thread pool size can no longer handle the work load of the server.

BEA-002957
Fair share request class "{0}" is configured with a fair share value of {1}, which is higher than the recommended maximum value of 100.

Category:
WorkManager

Cause:
The configured fair share value is higher than the recommended maximum value of 100.

Action:
Consider configuring a fair share value between 1 and 100 for the fair share request class.

BEA-002958
WorkManager state dump has been enabled.

Category:
WorkManager

Cause:
WorkManager state dump is enabled.

Action:
No action is required.

BEA-002959
Self-tuning thread pool contains {0} running threads, {1} idle threads, and {2} standby threads

Category:
WorkManager

Cause:
This is an informational message.

Action:
No action is required.

BEA-003000
Could not send cache multicast message for key "{0}", {1}.

Category:
Cache

Cause:
UThis error is usually caused by some communication failure.

Action:
Check the exception message for details.

BEA-003001
Leasing failure: {0}

Category:
Cache

Cause:
This error is usually caused by some communication failure.

Action:
Check the exception message for details.

BEA-003002
Replication failure: {0}

Category:
Cache

Cause:
This error is usually caused by some communication failure.

Action:
Check the exception message for details.

BEA-003004
Unexpected failure {0}

Category:
Cache

Cause:
This is a general purpose warning message.

Action:
No action is required. The cache will try to adjust to the failure.

BEA-003005
CacheFilter not caching the response for uri: {0} reason: {1}

Category:
Cache

Cause:
CacheFilter does not cache responses unless the status is 200.

Action:
Check the message for information on how to fix the problem.

BEA-003090
Could not send cache multicast message for key "{0}", {1}.

Category:
LLD

Cause:
This error is usually caused by some communication failure.

Action:
Check the exception message for details.

BEA-003101
Modified non-dynamic {0} property on the Administration Server.

Category:
Cluster

Cause:
The non-dynamic {0} property was updated while the server was in a running state.

Action:
Reboot the Administration Server so that the {0} property takes effect.

BEA-003102
There was a failure in the execution of the post script {0} while deactivating MigratableTarget {1}. Since post script failure is marked as fatal, the MigratableTarget will not be automatically migrated. To enable automigration, fix the post script failure and manually migrate the failed migratable target or disable the post script failure fatal flag.

Category:
Cluster

Cause:
The execution of the post deactivation script failed.

Action:
Fix the post deactivation script and migrate the MigratableTarget manually.

BEA-003103
{0} failed to release its lease because of {1}. This may affect its automatic migration behavior.

Category:
Cluster

Cause:
An exception occurred: {1}.

Action:
If a database is being used for leasing, ensure that it is available.

BEA-003104
Failed to notify the execution failure of the post script {1} for {0} to the SingletonServiceStateManager because of {2}. This may affect its automatic migration behavior.

Category:
Cluster

Cause:
An exception occurred: {2}.

Action:
Ensure that the network is working properly.

BEA-003105
The asynchronous replication request timed out while attempting to add object {0} to the replication queue. This session has not been replicated to any backup at this point.

Category:
Cluster

Cause:
The asynchronous replication request timed out while attempting to add object {0} to the replication queue. Once full, the queue waits until it has space for the object. This wait took longer than the ClusterMBean specified AsyncSessionQueueTimeout, thus the session object was not put into the queue and will not be replicated at this time.

Action:
This could be due to the secondary server or persistent store slowing down the replication process. To better handle this, the SessionFlushInterval and the SessionFlushThreshold can be reduced to replicate less at a time and to replicate more often. Checking the performance of the secondary server or persistent store is advised.

BEA-003106
An unexpected exception occured during replication: {0}. Future session updates should replicate as expected.

Category:
Cluster

Cause:
An unexpected runtime exception occured during replication probably from the Remote Management Interface (RMI) stub. Future session updates should replicate as expected.

Action:
Ensure that no problems exist in the network. If the problem persists, contact My Oracle Support and provide them with the stack trace for further analysis.

BEA-003107
Lost {0} unicast message(s).

Category:
Cluster

Cause:
This is an informational message. When a server joins a stable cluster, this message will appear since the server did not receive unicast messages sent out by other servers in the cluster.

Action:
No action is required.

BEA-003108
Unicast receive error : {0}

Category:
Cluster

Cause:
An error occurred while trying to receive a message over the cluster broadcast.

Action:
Ensure that the NIC is functioning properly. If it appears that no environment problems exist, contact My Oracle Support and provide the stack trace for further analysis.

BEA-003109
Cluster {0} uses a database as the migration basis but no data source for migration has been configured.

Category:
Cluster

Cause:
Cluster {0} uses a database as the migration basis but no data source for migration has been configured.

Action:
Ensure that the data source exists and is set for database migration basis.

BEA-003110
Connection attempt was rejected because the incoming protocol {1} is not enabled on channel {0}.

Category:
Cluster

Cause:
The connection attempt was rejected because the {1} protocol is not enabled at all for this server, as determined by the ServerMBean, or is not enabled on this particular channel.

Action:
Enable the {1} protocol on the channel.

BEA-003111
No channel exists for replication calls for cluster {0}.

Category:
Cluster

Cause:
No channel exists for replication calls for cluster {0}.

Action:
Configure the channels for replication calls.

BEA-003112
Channels "{0}" configured for replication traffic.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003113
Using one-way RMI for replication

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003114
Ignoring one-way RMI calls for replication because multiple replication channels are not present.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003115
Failed to synchronize a secondary session due to missing updates.

Category:
Cluster

Cause:
The Work Manager queue might be full and as a result update messages were dropped.

Action:
Either increase the number of servers in the cluster (preferred) or add more replication channels (requires server restart).

BEA-003116
Starting Member Death Detector.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003117
Starting Member Death Detector Heartbeat Receiver.

Category:
Cluster

Cause:
None.

Action:
None.

BEA-003118
WLS Server "{0}" does not have an associated machine configured. Member Death Detector will not be enabled for this server.

Category:
Cluster

Cause:
No associated machine configured with the server.

Action:
Please associate a machine with this server.

BEA-003119
The singleton service {0} is now registered on this server but will not be activated because this server is not part of a cluster.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003120
Hostname {0} failed to resolve during cluster initialization.

Category:
Cluster

Cause:
A name service such as DNS is unavailable or unstable.

Action:
Check the name service configuration or name service availability.

BEA-003121
Unicast cluster may not function correctly as the listen address of server {0} is not specified.

Category:
Cluster

Cause:
The listen address of the Managed Server was not specified.

Action:
Set the listen address of the Managed Servers.

BEA-003122
{0} : A cluster that has migratable servers could not create/execute an SQL statement when validating the database connection. The cluster is misconfigured. Check the leasing table on the database and connection configuration.

Category:
Cluster

Cause:
The cluster is not configured correctly.

Action:
Check the leasing table in the database and connection configuration.

BEA-003123
Singleton Monitor has detected that the singleton service {0} is in a failed state.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003124
Singleton Monitor has detected that the singleton service {0} has an expired status.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003125
Singleton Monitor has detected that the singleton service {0} has no lease.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003126
{0} will attempt to auto-migrate.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003127
{0} will attempt to restart in place on server {1}.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003128
{0} has been completed to restart in place.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003129
{0} will attempt to auto-migrate from {1} to {2}.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003130
{0} successfully activated on server {1}.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003131
The singleton service {0} has failed with failure state : {1}. Summary of reason Code : {2}

Category:
Cluster

Cause:
A critical service has failed, most likely due to an exception.

Action:
Depending on the cause, corrective action must be taken to resolve the failure. If the problem still persists, contact My Oracle Support for further analysis.

BEA-003132
An EJB is configured to use the clustered EJB timer implementation but the data-source-for-job-scheduler cluster attribute is not configured.

Category:
Cluster

Cause:
While deploying an EJB, the EJB container determined that the data-source-for-job-scheduler cluster attribute has not been set.

Action:
You must either set the timer-implementation attribute of your weblogic-ejb-jar.xml descriptor to Local or configure the data-source-for-job-scheduler attribute for your cluster.

BEA-003133
An EJB is configured to use the clustered EJB timer implementation but the data-source-for-job-scheduler attribute is not configured in partition "{0}".

Category:
Cluster

Cause:
While deploying this EJB, the EJB container determined that the data-source-for-job-scheduler partition attribute has not been set.

Action:
You must either set the timer-implementation attribute of your weblogic-ejb-jar.xml descriptor to Local or configure the data-source-for-job-scheduler attribute for your partition.

BEA-003134
An EJB is configured to use the clustered EJB Timer implementation but this server is not part of a cluster.

Category:
Cluster

Cause:
You cannot deploy an EJB that uses clustered EJB timers to a server that is not part of a cluster.

Action:
You must either set the timer-implementation attribute of your weblogic-ejb-jar.xml descriptor to Local or ensure that any servers to which you deploy the EJB are part of a cluster.

BEA-003135
Job Scheduler service was not started for this partition because the data source for the job scheduler is not configured for this partition.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required unless the job scheduler service is needed in this partition, in which case you can configure a data source for the job scheduler for this partition and restart the partition.

BEA-003136
Job scheduler service was not started for this partition because this server does not belong to a cluster.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003137
Server in cluster {0} was unable to bind MulticastSocket to address {0}. Will bind to IP_ANY instead.

Category:
Cluster

Cause:
This was caused by an invalid multicast IP address.

Action:
Configure the cluster to use a valid multicast IPv4 or IPv6 address.

BEA-003138
Synchronized {1} from server {0}.

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003139
AssertionError is raised on installing ServiceOffer from remote node : {0}

Category:
Cluster

Cause:
Internal data structure is corrupted.

Action:
If there is no other problems, no action is required. Corrupted offer will be simply ignored.

BEA-003140
Partition {0} from server {1} {2} for cluster view {3}

Category:
Cluster

Cause:
The partition has been started/stopped on a particular server in the cluster

Action:
No action is required

BEA-003141
Thread {0} attempted a re-entrant call to the WLS Replication Service while actively replicating session state to a secondary server.

Category:
Cluster

Cause:
During replication of the application''s session state, an attempt was made by the same thread to access the same session instance that is actively being serialized..

Action:
None

BEA-003142
An exception occurred while ensuring replica {0} replicated: {1}

Category:
Cluster

Cause:
An exception occurred while ensuring replica {0} replicated: {1}

Action:
Please check the exception for the exact error message.

BEA-003143
An exception occurred while locally cleaning up replica {0} for replication key {1}: {2}

Category:
Cluster

Cause:
An exception occurred while locally cleaning up replica {0} for replication key {1}: {2}

Action:
Please check the exception for the exact error message.

BEA-003144
All session objects should be serializable to replicate. Check the objects in the session. Failed to replicate a non-serializable object in context {0}.

Category:
Cluster

Cause:
Objects in the session are not serializable or externalizable.

Action:
Ensure that all user-defined objects in the HTTP session are serializable.

BEA-003145
An exception occurred while starting TimerMaster for {0}: {1}

Category:
Cluster

Cause:
An exception occurred while starting TimerMaster service for job scheduler for {0}. The exception is {1}

Action:
Please check the exception for the cause and take appropriate action.

BEA-003146
Unicast cluster may not function correctly as the listen address of server {0} is not specified.

Category:
Cluster

Cause:
The listen address of the Managed Server was not specified.

Action:
Set the listen address of the Managed Servers.

BEA-003147
Detected Exception occurred when calling {0} method. Timer info: {1}

Category:
Cluster

Cause:
An exception occurred: {2}.

Action:
See transaction error and check the root cause

BEA-003148
The Clustered Timer: {0} has failed to successfully time out in {1} consecutive attempts. Scheduler will automatically delay the timeout for {2} seconds. Timer info: {3}

Category:
Cluster

Cause:
This is an informational message.

Action:
No action is required.

BEA-003149
Failed to fire retry timer because of Leasing problem and reset retry state. Timer info: {0}

Category:
Cluster

Cause:
An exception occurred: {1}.

Action:
If the problem persists, contact My Oracle Support and provide them with the stack trace for further analysis.

BEA-003150
Server "{0}" has acquired the role of Singleton Master for the cluster.

Category:
Cluster

Cause:
TBD

Action:
TBD

BEA-003151
Server "{0}" is no longer the Singleton Master for the cluster.

Category:
Cluster

Cause:
TBD

Action:
TBD

BEA-003501
The migration of server {0} from machine {1} has failed. No suitable candidate machines could be found.

Category:
Cluster

Cause:
No candidate machines are available, or the server {0} has encountered an error on booting independent of its location.

Action:
Further migration of server {0} has been disabled. When the cause of the problem has been determined and fixed, the server {0} should be started by the user, at which point it will resume standard automatic migration behavior.

BEA-003502
Beginning the migration of server {0} from machine {1} to machine {2}

Category:
Cluster

Cause:
The failure of server {0} has provoked a migration attempt to a new machine, machine {2}.

Action:
No action is required, but the logs of server {0} should be examined to determine why it crashed and could not successfully restart on machine {1}.

BEA-003503
The migration of server {0} from machine {1} to machine {2} has succeeded.

Category:
Cluster

Cause:
The failure of server {0} provoked a migration attempt to a new machine, machine {2}. The migration is now complete.

Action:
No action is required.

BEA-003504
The migration of server {0} from machine {1} to machine {2} has failed, because machine {2} is not reachable.

Category:
Cluster

Cause:
Machine {2} was not reachable. A new machine for server {0} will be chosen.

Action:
No action is required.

BEA-003800
Could not parse the user random seed property whose value is {0}. Using seed {1}

Category:
WebLogicServer

Cause:
The seed used to randomize startup services was not parseable. The seed is given to the server with the com.oracle.weblogic.debug.RandomizeServerServices.seed system property.

Action:
Check the value of the com.oracle.weblogic.debug.RandomizeServerServices.seed property given to the server, and make sure it can be parsed into a valid long value

BEA-003801
Could not read server service randomizer file {0}. The seed used in this run is randomSeed

Category:
WebLogicServer

Cause:
The seed file used to randomize startup services was not parseable. The name of the seed file is given to the server with the com.oracle.weblogic.debug.RandomizeServerServices.filename system property.

Action:
Check the value of the com.oracle.weblogic.debug.RandomizeServerServices.filename property given to the server, and make sure it points to a file that contains one line that can be parsed into a long which should be used for the random seed

BEA-003802
The order in which the server services are started has been randomized with seed {0}{1}

Category:
WebLogicServer

Cause:
The server service randomizer was used to randomize server services with the given seed

Action:
No action necessary

BEA-003803
Could not write server service randomizer file {0}. The seed used in this run is {1}

Category:
WebLogicServer

Cause:
When using the service randomizer the system attempted to write the seed used to a file for later use, but the system could not write the file

Action:
Ensure that the randomizer file is in a directory where the system can write and that there is enough disk space in that file system

BEA-003804
The randomizer file with location {0} is not readable. The seed used in this run is {1}

Category:
WebLogicServer

Cause:
The randomizer file at the given location is not readable

Action:
Ensure that the randomizer file is readable by the system

BEA-003805
The data found in randomizer file with location {0} is not parseable into a long. The seed used in this run is {1}

Category:
WebLogicServer

Cause:
The randomizer file at the given location has bad data in it

Action:
Ensure that the randomizer file has one line that can be parsed into a long value

BEA-003806
There was an error redirecting {0}. The stream will not be redirected.

Category:
WebLogicServer

Cause:
This is caused due to an I/O error in initializing the new stream.

Action:
Correct the error based on the exception messages reported and restart the server.

BEA-004501
Bootstrap request was rejected from server {0} of cluster {1}.

Category:
ConsensusLeasing

Cause:
Server configuration parameters, such as listen-address and port, are duplicated between servers in different clusters.

Action:
Change server configuration parameters of the servers in the domain.

BEA-004502
Exception occurred during unicast connection bootstrapping: {0}

Category:
ConsensusLeasing

Cause:
See displayed exception.

Action:
Report this error to My Oracle Support.

BEA-010000
Exception occurred during ejbActivate: {0}

Category:
EJB

Cause:
An error occurred while calling ejbActivate() on the bean.

Action:
Check your implementation of the ejbActivate method.

BEA-010001
While deploying EJB "{0}", class {1} was loaded from the system classpath. As a result, this class cannot be reloaded while the server is running. To prevent this behavior in the future, make sure the class is not located in the server classpath.

Category:
EJB

Cause:
The specified class is located in the server classpath.

Action:
Remove this class from the server classpath. It should only be located in the packaged application.

BEA-010002
An error occurred while undeploying: {0}.

Category:
EJB

Cause:
An error occurred while undeploying.

Action:
Please check the exception for the exact error message.

BEA-010003
Exception occurred while loading _WL_TIMESTAMP FILE.

Category:
EJB

Cause:
The container generates the _WL_GENERATED file, which stores the server version of the appc compiler. If the current server version is different from the version specified in the _WL_GENERATED file, appc recompiles the beans. There was an error reading this file.

Action:
The container will automatically recompile the beans.

BEA-010006
Error occurred while saving ejb deployment timestamps. {0}

Category:
EJB

Cause:
The container generates the _WL_GENERATED file, which stores the server version of the appc compiler. if the current server version is different from the version specified in the _WL_GENERATED file, appc recompiles the beans. There was an error writing this file.

Action:
Please check the exception for the exact error message. The container will recompile the beans if this file is not found.

BEA-010007
License validation passed for {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action required.

BEA-010008
EJB Deploying file: {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action required.

BEA-010009
EJB deployed EJB with JNDI name {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action required.

BEA-010011
Exception looking up current transaction: {0}

Category:
EJB

Cause:
See the message body.

Action:
No action required.

BEA-010012
Exception looking up current transaction: {0}

Category:
EJB

Cause:
See the message body.

Action:
No action required.

BEA-010014
Error occurred while attempting to rollback transaction: {0}

Category:
EJB

Cause:
There was an error when rolling back the transaction.

Action:
Please check the exception for the exact error message.

BEA-010015
Error occurred while marking transaction for rollback: {0}.

Category:
EJB

Cause:
The container was unable to mark the transaction for rollback.

Action:
Please check the exception for exact error message.

BEA-010016
Exception occurred while marking transaction for rollback: {0}.

Category:
EJB

Cause:
The container was unable to mark the transaction for rollback.

Action:
Please check the exception for the exact error message.

BEA-010017
Exception occurred during rollback of transaction {0}: {1}.

Category:
EJB

Cause:
The container was unable to rollback the transaction.

Action:
Please check the exception for the exact error message.

BEA-010018
Error occurred while resuming caller transaction: {0}

Category:
EJB

Cause:
The container was unable to resume the transaction.

Action:
Please check the exception for the exact error message.

BEA-010019
Running in a cluster, but DNS name of cluster is not set. This may prevent EJB handles from operating properly.

Category:
EJB

Cause:
The DNS name of the cluster is not set.

Action:
Set the DNS cluster name.

BEA-010020
EJB-20 - MessageDriven - Could not start the JMS connection: {0}

Category:
EJB

Cause:
The JMS provider may not be available, or the Message-Driven Bean deployment descriptors or annotation or both may not be correct.

Action:
Verify that the JMS provider is running and accessible through the network. Verify that the deployment descriptors or annotation or both specify the correct configuration information for the JMS provider.

BEA-010022
Error occurred in ejbPassivate: {0}.

Category:
EJB

Cause:
There was an error passivating the bean.

Action:
Please check the exception for the exact error message. Verify the implementation of the ejbPassivate method in the bean.

BEA-010024
Error occurred during passivation: {0}

Category:
EJB

Cause:
The container was unable to passivate the bean.

Action:
Check the exception for the exact error message.

BEA-010025
Exception occurred during rollback of transaction {0}: {1}

Category:
EJB

Cause:
An error occurred when rolling back the transaction.

Action:
Check the exception for the exact error message.

BEA-010026
Exception occurred during commit of transaction {0}: {1}.

Category:
EJB

Cause:
An error occurred when committing the transaction.

Action:
Check the exception for the exact error message.

BEA-010029
Exception occurred during commit of transaction {0}: {1}.

Category:
EJB

Cause:
An error occurred while committing the transaction.

Action:
Check the exception for the exact error message.

BEA-010030
Ignoring exception that occurred when rolling back a transaction during undeployment of {0}.

Category:
EJB

Cause:
An error occurred while undeploying the bean.

Action:
Check the exception for the exact error message.

BEA-010031
EJB exception in method: {0}: {1}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010032
Exception during ejbActivate(): {0}

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010033
Exception from ejbLoad: {0}

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010034
Exception from ejbStore: {0}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010036
Exception from ejbStore: {0}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010038
Exception from __WL_superEjbLoad: {0}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010039
Exception in ejbStore: {0}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010040
Exception in ejbStore: {0}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010043
Exception in ejbActivate: {0}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010044
Exception trying to resume transaction: {0}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010045
Exception in afterBegin: {0}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010046
Exception in beforeCompletion: {0}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010047
Exception during setRollbackOnly: {0}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010048
Exception in afterCompletion: {0}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010049
EJB exception in method: {0}: {1}.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010050
A stateless session bean with bean-managed transactions must commit or roll back a transaction before the business method completes.

Category:
EJB

Cause:
See the message body.

Action:
Check the exception for the exact error message.

BEA-010051
EJB exception occurred during invocation from home: {0} generated exception: {1}

Category:
EJB

Cause:
See the message body.

Action:
No action required.

BEA-010052
An exception occurred while creating the free pool for EJB {0}. Since this occurred during server startup, when a dependent resource may be unavailable, the error will be ignored and deployment will proceed. The EJB container will instead attempt to create the bean instances on demand. The exception was: {1}

Category:
EJB

Cause:
An exception occurred while the EJB container was initializing the free pool of bean instances. The root exception should be printed as part of the warning message issued by the EJB container. Check the server log for further details.

Action:
If you believe the root exception is due to a temporary condition that will automatically be resolved, no action is required. If this exception was not due to a temporary condition, fix the cause of the root exception. If changes to your application are required to fix this issue, redeploy the updated application.

BEA-010054
EJB deployment: {0} has a class {1} that is in the classpath. This class should only be located in the ejb-jar file.

Category:
EJB

Cause:
{1} is in the classpath.

Action:
Remove this class from the classpath. It should only be in the ejb-jar.

BEA-010055
Could not load the RDBMS deployment descriptor for EJB {0} from the file {1}. The file was not found in the JAR file {2}.

Category:
EJB

Cause:
{1} is missing from the JAR file.

Action:
Please add the missing file to the JAR file.

BEA-010057
Could not find a license for EJB 3.0. Please contact Oracle to get a license.

Category:
EJB

Cause:
Unable to get license for EJB 3.0.

Action:
Contact Oracle to get a license.

BEA-010058
The EJB deployment named {0} is being recompiled within the WebLogic Server instance. Please consult the server logs if there are any errors. It is also possible to run weblogic.appc as a standalone tool to generate the required classes.

Category:
EJB

Cause:
See the message body.

Action:
No action required.

BEA-010059
An error occurred while attempting to invalidate the target Read-Only Entity EJB: {0}. The error was: {1}

Category:
EJB

Cause:
The invalidation of read-only beans failed.

Action:
Check the message for the cause.

BEA-010060
The Message-Driven EJB {0} has connected or reconnected to the JMS destination {1}.

Category:
EJB

Cause:
The JMS connection has been re-established.

Action:
No action is required.

BEA-010061
The Message-Driven EJB {0} is unable to connect to the JMS destination {1}. The Error was: {2}

Category:
EJB

Cause:
The JMS destination is not available due to a network problem or a problem with the JMS provider, or the configuration information in the MDB deployment descriptor or annotation or both is incorrect. This warning may also occur during WebLogic cluster startup if the JMS destination is located on another server.

Action:
Check that the JMS provider is running and that network connectivity is available. Also check that the configuration information in the MDB deployment descriptor and/or annotation is correct.

BEA-010065
MessageDrivenBean threw an Exception in onMessage(). The exception is: {0}.

Category:
EJB

Cause:
The onMessage method of the MDB may have generated an exception for a legitimate reason, such as the loss of a database connection. If that is not the case, then the MDB may have a programming error that causes it to generate an unchecked Java exception, such as a NullPointerException.

Action:
Unless you are sure that the MDB has generated the exception on purpose, check the source code to ensure that it does not contain any programming errors that might cause it to generate an unchecked Java exception such as a NullPointerException or IndexOutOfBoundsException.

BEA-010066
The Entity EJB {0} generated an exception when its unsetEntityContext was called. This error is ignored by the EJB container. The error is: {1}

Category:
EJB

Cause:
See the message body.

Action:
No action required.

BEA-010067
Exception during ejbRemove: {0}

Category:
EJB

Cause:
See the message body.

Action:
No action required.

BEA-010071
Error occurred while performing Pop of Caller Principal: {0}

Category:
EJB

Cause:
This is a possible internal container error.

Action:
Check the security settings related to the run-as roles and principals setting.

BEA-010072
Error occurred while starting EJB module {0}. Exception is: {1}

Category:
EJB

Cause:
The container was unable to start the EJB module.

Action:
Check the exception for the exact error message.

BEA-010073
Unable to add the {0} interface "{1}" and any dependent classes to the client-jar since it was loaded from the classpath.

Category:
EJB

Cause:
EJB interface and other dependent classes exist in the system classpath.

Action:
Please remove the classes from the system classpath.

BEA-010074
Unable to create the client-jar file due to classes being loaded from the classpath rather than the input JAR. Please modify your classpath so that it does not contain these classes and try again.

Category:
EJB

Cause:
EJB interface and other dependent classes exist in the system classpath.

Action:
Please modify your classpath so it does not contain these classes and try again.

BEA-010075
Skipping creation of the client-jar since no EJBs with a remote client view are contained in the JAR file.

Category:
EJB

Cause:
See the message body.

Action:
No action required.

BEA-010076
Client-jar {0} created.

Category:
EJB

Cause:
See the message body.

Action:
No action required.

BEA-010079
An error occurred while attempting to receive a message from JMS for processing by a Message-Driven Bean: {0} The exception is : {1}

Category:
EJB

Cause:
The JMS provider for the MDB may have been shut down or has crashed, or network connectivity may have been lost.

Action:
Check that the JMS provider is available and accessible through the network.

BEA-010080
An error occurred while attempting to process a message inside a Message-Driven Bean: {0} Exception is : {1}

Category:
EJB

Cause:
This error usually occurs if the onMessage method of the MDB throws an exception.

Action:
Check that the MDB is able to process messages by ensuring that any resources it uses (such as database connections) are available. Check the MDB source code to ensure that it does not have any bugs that cause an exception (such as a NullPointerException) to be generated.

BEA-010081
The Message-Driven Bean {0} was configured to use a JMS Topic, requires container-managed transactions, and uses a foreign JMS provider. Only one thread will be used to receive and process all messages.

Category:
EJB

Cause:
The nature of the JMS API does not permit this in a standard way.

Action:
No action is required. However, if you require better performance for a foreign JMS provider and do not need exactly-once transactional semantics, redeploy the MDB so that it has a transaction mode of NotSupported.

BEA-010082
Failed to undeploy security role for resource {0}, while undeploying EJB.

Category:
EJB

Cause:
Unable to remove the role from the security layer.

Action:
Check the exception for the exact error message.

BEA-010083
Failed to undeploy security policy for resource {0}, while undeploying EJB.

Category:
EJB

Cause:
The policy could not be removed from the security layer.

Action:
Check the exception for the exact error message.

BEA-010084
The Message-Driven Beans are being suspended. This may take a minute or two.

Category:
EJB

Cause:
The server is being suspended or shut down.

Action:
No action is required.

BEA-010085
The Message-Driven Beans have all been suspended.

Category:
EJB

Cause:
The server is being suspended or shut down.

Action:
No action is required.

BEA-010086
The deployment unit {0} that contains Message-Driven Beans is undeployed already. The server cannot start the Message-Driven Beans that are part of undeployed unit.

Category:
EJB

Cause:
The beans were started after having been undeployed.

Action:
No action is required.

BEA-010087
The EJB deployment named {0} is being recompiled within the WebLogic Server instance. Please consult the server logs if there are any errors. It is also possible to run weblogic.appc as a standalone tool to generate the required classes. The generated source files will be placed in {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-010088
Could not find a license for in-memory replication of the EJB. This feature is disabled.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-010089
Failed to create copy of bean {0} with error: {1}.

Category:
EJB

Cause:
The server was unable to create the secondary server.

Action:
Check the exception for the exact error message.

BEA-010090
Failed to update secondary copy with: {0}

Category:
EJB

Cause:
The server was unable to update the secondary.

Action:
Check the exception for the exact error message.

BEA-010091
Failure during stateful session bean replication: {0}

Category:
EJB

Cause:
The container was unable to replicate the stateful session bean.

Action:
Check the exception for the exact error message.

BEA-010092
Failure while updating secondary server during replication of {0}. The error was: {1}

Category:
EJB

Cause:
The server was unable to update the secondary server.

Action:
Check the exception for the exact error message.

BEA-010094
Failed to update the secondary copy of a stateful session bean from home {0}.

Category:
EJB

Cause:
The server was unable to update the secondary server.

Action:
Check the exception for the exact error message.

BEA-010096
The Message-Driven EJB {0} is unable to connect to the JMS destination or bind to JCA resource adapter {1}. The connection failed after {2} attempts. The MDB will attempt to reconnect/rebind every {3} seconds. This log message will repeat every {4} seconds until the condition clears.

Category:
EJB

Cause:
The JMS provider or JCA resource adapter is not available, or the configuration is incorrect and WebLogic Server is not able to connect.

Action:
Ensure that the JMS provider is running and is reachable using the network, or the JCA resource adapter is deployed. Also ensure that the configuration information in the MDB deployment descriptor or the annotation or both are correct.

BEA-010097
Exception occurred during the invocation of EJB {0} with primary key {1}.

Category:
EJB

Cause:
The bean generated a system exception.

Action:
Check the exception for the exact error message.

BEA-010098
The database type {0} mentioned in weblogic-cmp-rdbms-jar.xml does not match the database type returned by the driver {1}.

Category:
EJB

Cause:
The database type {0} mentioned in weblogic-cmp-rdbms-jar.xml does not match the database type returned by the driver {1}.

Action:
Check the database-type tag inside weblogic-cmp-rdbms-jar.xml.

BEA-010099
WARNING(S) from EJB QL Compiler. {0}

Category:
EJB

Cause:
The compilation of EJB-QL succeeded. These are some non-fatal warnings.

Action:
Check the message for the exact warnings.

BEA-010100
This server is not part of a cluster. Therefore the InMemory replication feature for StatefulSession EJB {0} will have no effect on this server.

Category:
EJB

Cause:
The bean has been deployed on a server, which is not a part of cluster. Hence the InMemory replication feature will be ignored.

Action:
No action is required.

BEA-010102
Error encountered while attempting to create default DBMS table {0}. Error text: {1}

Category:
EJB

Cause:
An error was encountered while attempting to create the default DBMS table.

Action:
Take appropriate action based on the logged error message.

BEA-010124
Method SecurityHelper.{0} returned a NULL principal. The CallerPrincipal stack has been corrupted.

Category:
EJB

Cause:
One cause of corruption might be that a bean has created its own threads. Note that this would be in violation of EJB2.0 Final Spec Chapter: Runtime Management 24.1.2.

Action:
Review your code about thread safety. If a bean does not create its own thread, this is likely a bug in the EJB subsystem and you should probably contact My Oracle Support.

BEA-010127
Incorrect data source type detected. The data source with JNDI name {0}, specified in the RDBMS deployment descriptor for the EJB {1}, does not support global transactions.

Category:
EJB

Cause:
The EJB container requires that a data source which supports global transactions be specified for transactions to be managed correctly.

Action:
Specify the correct data source for the EJB.

BEA-010128
Error during deployment of EJB {0}. The EJB references an application-level cache, {1}, that is not defined in the weblogic-application.xml descriptor.

Category:
EJB

Cause:
The weblogic-ejb-jar.xml descriptor for the EJB refers to an unknown application-level cache.

Action:
Ensure that the application-level cache is defined in the weblogic-application.xml descriptor and ensure the cache name defined in the weblogic-ejb-jar.xml is correct.

BEA-010129
Error during deployment of EJB {0}. The EJB references a MultiVersion application-level cache {1}, but it must use an Exclusive cache instead. EJBs with a concurrency-strategy of Exclusive must use an Exclusive cache.

Category:
EJB

Cause:
An incorrect concurrency strategy is specified. The concurrency-strategy you specify for the bean must be compatible with the caching-strategy specified in weblogic-application.xml.

Action:
Specify the correct concurrency strategy.

BEA-010130
An error occurred during deployment of EJB {0}. The EJB references an Exclusive application level cache {1}, but it must use a MultiVersion cache instead. EJBs with a concurrency-strategy of Database, ReadOnly, or Optimistic must use a MultiVersion cache.

Category:
EJB

Cause:
An incorrect concurrency strategy is specified. The concurrency-strategy you specify for the bean must be compatible with the caching-strategy specified in weblogic-application.xml.

Action:
Specify the correct concurrency strategy.

BEA-010132
Error during deployment of EJB {0}. The EJB has been deployed with use-select-for-update set to true. The database indicates it does not support SELECT ... FOR UPDATE.

Category:
EJB

Cause:
The database indicates it does not support SELECT ... FOR UPDATE.

Action:
Modify use-select-for-update to false, or use a different database that supports SELECT ... FOR UPDATE.

BEA-010139
Bean with primary key {0} already exists.

Category:
EJB

Cause:
A bean with the indicated primary key value already exists.

Action:
Do not use a non-unique value as a primary key.

BEA-010141
Creation of Many-To-Many relationship for primary key: {0} and {1} effected {2} rows in {3}, instead of just 1.

Category:
EJB

Cause:
JoinTable contains a non-unique row for specified primary keys, indicating a Many-To-Many relationship.

Action:
Check the JoinTable to remove the duplicate row.

BEA-010144
The setXXX method for a primary key field may only be called during ejbCreate.

Category:
EJB

Cause:
The setXXX method for a primary key field may only be called during ejbCreate.

Action:
Remove the setXXX method call (for a primary key field) from places other than ejbCreate.

BEA-010145
When a cmp-field and a cmr-field (relationship) are mapped to the same column, the setXXX method for the cmp-field may not be called.

Category:
EJB

Cause:
The cmp-field is read-only.

Action:
Remove the setXXX method call if cmp-filed is also used as cmr-field.

BEA-010146
The setXXX method for a cmr-field that is mapped to a primary key may not be called.

Category:
EJB

Cause:
The cmr-field is read-only.

Action:
Remove the setXXX method call if it is cmr-field mapped to a primary key.

BEA-010147
The setXXX method for a cmr-field may not be called during ejbCreate. The setXXX method should be called during ejbPostCreate instead.

Category:
EJB

Cause:
The setXXX method should be called during ejbPostCreate instead.

Action:
Move the setXXX method call for a cmr-field to ejbPostCreate.

BEA-010148
In EJB {0}, the primary key field {1} was not set during ejbCreate.

Category:
EJB

Cause:
All primary key fields must be initialized during ejbCreate.

Action:
Be sure to initialize the primary key field during ejbCreate.

BEA-010149
According to the EJB 2.0 specification, a value of "null" may not be assigned to a collection valued cmr-field.

Category:
EJB

Cause:
This violates the EJB 2.0 specification.

Action:
Avoid using a null argument for a collection valued cmr-field.

BEA-010152
Illegal value for concurrency-strategy. Value was {0}, but must be one of ReadOnly, Exclusive, Database, or Optimistic.

Category:
EJB

Cause:
An illegal value was used for concurrency-strategy.

Action:
Specify a correct value for concurrency-strategy. It must be one of ReadOnly, Exclusive, Database, or Optimistic

BEA-010153
Only instances of beans with a remote client view can invoke getEJBObject().

Category:
EJB

Cause:
See the error message body.

Action:
Remove the getEJBObject() method call from the local client.

BEA-010154
Only instances of beans with a local client view can invoke getEJBLocalObject().

Category:
EJB

Cause:
See the error message body.

Action:
Remove the getEJBLocalObject() method call from remote client.

BEA-010155
Only instances of beans with container-managed transaction demarcation can use getRollbackOnly().

Category:
EJB

Cause:
See the error message body.

Action:
Remove the getRollbackOnly() method call if container-managed transaction is not used, or enable container-managed transaction for EJB.

BEA-010156
Illegal attempt to call EJBContext.getRollbackOnly() from an EJB that was not participating in a transaction

Category:
EJB

Cause:
See the error message body.

Action:
Make sure to begin the transaction before calling the getRollbackOnly() method.

BEA-010157
Only instances of beans with container-managed transaction demarcation can use setRollbackOnly().

Category:
EJB

Cause:
See the error message body.

Action:
Remove the setRollbackOnly() method call if container-managed transaction is not used, or enable container-managed transaction for EJB.

BEA-010158
Illegal attempt to call EJBContext.setRollbackOnly() from an EJB that was not participating in a transaction

Category:
EJB

Cause:
See the error message body.

Action:
Begin the transaction before calling the setRollbackOnly() method.

BEA-010159
To support the use of Handles and HomeHandles, an EJB must be deployed with a JNDI name. This EJB, {0}, was deployed without specifying a JNDI name. To specify a JNDI name for this EJB, add a jndi-name element to the weblogic-ejb-jar.xml deployment descriptor or corresponding annotation for this EJB.

Category:
EJB

Cause:
This EJB, {0}, was deployed without specifying a JNDI name.

Action:
To specify a JNDI name for this EJB, add a jndi-name element to the weblogic-ejb-jar.xml deployment descriptor or corresponding annotation for this EJB.

BEA-010160
Security violation: User {0} has insufficient permission to access EJB {1}.

Category:
EJB

Cause:
The specified user has insufficient permission to access the EJB.

Action:
Grant sufficient permissions to the user to enable to access the EJBResource.

BEA-010166
Error occurred while starting transaction: {0}.

Category:
EJB

Cause:
An exception occurred while starting the Message-Drive Bean transaction.

Action:
Take appropriate action based on the text of the exception message.

BEA-010167
Message-Driven Beans are not allowed to call {0}.

Category:
EJB

Cause:
The method is unavailable for MDBs.

Action:
Remove the method call from the MDBs.

BEA-010168
Method {0} has been declared in an assembly-descriptor exclude-list and cannot be executed.

Category:
EJB

Cause:
The specified method is declared in the exclude-list.

Action:
Remove the method name from the exclude-list or remove the method call.

BEA-010173
env-entry for type java.lang.Character had length = 0.

Category:
EJB

Cause:
If there is env-entry for type java.lang.Character, the parameter value should not be length = 0.

Action:
Use a non-zero length value for java.lang.Character env-entry.

BEA-010188
Error encountered while attempting to drop Default DBMS Table {0}.

Category:
EJB

Cause:
See the exception stack trace included in the logged message.

Action:
Take appropriate action based on the exception stack trace in the logged message.

BEA-010189
Error encountered while attempting to alter Default DBMS Table: {0}.

Category:
EJB

Cause:
See the exception stack trace included in the logged message.

Action:
Take appropriate action based on the exception stack trace in the logged message.

BEA-010191
The alter table option is not supported in {0}. Use the DropAndCreate option.

Category:
EJB

Cause:
The alter table option is not supported in the given database.

Action:
Use the DropAndCreate option.

BEA-010194
Only instances of beans with bean-managed transaction demarcation can use getUserTransaction().

Category:
EJB

Cause:
An illegal invocation was made to the getUserTransaction() method on a Container Managed Bean.

Action:
Remove the getUserTransaction() method call from EJBs that are using container-managed transaction.

BEA-010195
Security violation: User {0} has insufficient permission to access method {1}.

Category:
EJB

Cause:
The specified user has insufficient permission to access the specified method.

Action:
Grant sufficient permissions to the user to enable access to the method.

BEA-010197
The entity bean {0} uses optimistic concurrency with read-verification enabled. The database indicates that exclusive row locks are not supported. Read-verification will not guarantee data integrity if the isolation level of the transaction is lower than repeatable read.

Category:
EJB

Cause:
This is a mismatch problem between the concurrency strategy and the transaction isolation level.

Action:
If data integrity should be guaranteed under a read-verification enabled configuration, use the appropriate transaction isolation level.

BEA-010198
An exception occurred while uninitializing the EJB module {0}.

Category:
EJB

Cause:
Check the exception for the exact cause.

Action:
Check the exception for the exact error message, and take appropriate action.

BEA-010199
EJB {0} with run as role {1} has no run-as-principal-name specified in its deployment descriptor or annotation. The EJB container has chosen principal-name {2} from the security-role-assignment list for role {1} to be the run as principal name.

Category:
EJB

Cause:
The specified EJB with the specified run as role has no run-as-principal-name specified in its deployment descriptor or annotation.

Action:
Specify run-as-principal-name explicitly if the chosen principal-name is not the appropriate one.

BEA-010201
The Message-Driven Bean {0} encountered an error while recovering a JMS session. This is a secondary error. The original error occurred while the Message-Driven Bean was processing a message. The recover action was taken in an attempt to recover from the original error, which will be logged separately.

Category:
EJB

Cause:
The Message-Driven Bean may have generated an exception, or there may be a problem with the JMS provider.

Action:
Check that the JMS provider is running and accessible through the network. In addition, check that the Message-Driven Bean onMessage method does not generate any unchecked Java exceptions such as NullPointerException or IndexOutOfBoundsException.

BEA-010202
Call-by-reference is not enabled for EJB {0}. The server will have better performance if it is enabled. To enable call-by-reference, set the enable-call-by-reference element to True in the weblogic-ejb-jar.xml deployment descriptor or corresponding annotation for this EJB.

Category:
EJB

Cause:
Call-by-reference is not enabled.

Action:
If appropriate, enable call-by-reference in the weblogic-ejb-jar.xml deployment descriptor or corresponding annotation for the EJB.

BEA-010204
The EJB component, {0}, will be rolled back and redeployed to update class {1}. This class is not a bean implementation class. Only bean implementation classes can be updated without redeploying the entire module, and only when enable-bean-class-redeploy is set to True in weblogic-ejb.jar.xml.

Category:
EJB

Cause:
A command was issued to update the specified class.

Action:
No action is necessary. This is just an informative message indicating why the EJB module is being redeployed, since this can cause disruption to clients using an EJB in this EJB module.

BEA-010205
The EJB module, {0}, will be rolled back and redeployed to update the class {1}. Bean implementation classes, such as this, can be updated without redeploying the entire EJB module. However, this can only be done if enable-bean-class-redeploy is set to True in weblogic-ejb.jar.xml or the corresponding annotation. If this is the behavior you want, set this value to True and redeploy.

Category:
EJB

Cause:
A command was issued to update the specified class.

Action:
No action is necessary. This is just an informative message indicating why the EJB module is being redeployed since this can cause disruption to clients using an EJB in this EJB module.

BEA-010206
The EJB module, {0}, will be rolled back and redeployed to update the class {1}. This bean implementation class could not be updated without redeploying the entire EJB module because it was changed incompatibly. Incompatible changes are any changes that cause the EJB compiler to be run. This includes modifying a public variable name or a public method signature.

Category:
EJB

Cause:
A command was issued to update the specified class.

Action:
No action is necessary. This is just an informative message to let the user know why the EJB module is being redeployed since this can cause disruption to clients using an EJB in this EJB module.

BEA-010207
License validation not passed for {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-010208
ddl-file {0} created.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-010209
ddl-file {0} could not be deleted.

Category:
EJB

Cause:
See the message body.

Action:
Check the file permissions.

BEA-010210
Unable to write to ddl-file {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-010211
Unable to alter the table, as the primary key has changed.

Category:
EJB

Cause:
See the message body.

Action:
Use the DropAndCreate option to create the table.

BEA-010212
The EJB {0} contains at least one method without an explicit transaction attribute setting. The default transaction attribute of {1} will be used for the following methods: {2}.

Category:
EJB

Cause:
The ejb-jar.xml deployment descriptor or corresponding annotation does not contain transaction attribute settings for the specified EJB methods.

Action:
Assign transaction attributes for all methods of your EJB.

BEA-010213
Message-Driven EJB: {0}"s transaction was rolled back, because {1}. The transaction details are: {2}.

Category:
EJB

Cause:
The transaction was rolled back by the MDB container.

Action:
This is an informational message. No action is needed.

BEA-010214
Error starting MDB {0}.

Category:
EJB

Cause:
This error itself does not provide the cause of the error. The log file will contain an exception stack indicating the root cause of the failure.

Action:
Inspect the log file for indications of the root cause of the failure.

BEA-010215
The durable subscription store with jms-client-id equal to {0} is deleted when MDB {1} is removed from the server.

Category:
EJB

Cause:
The durable subscription store is deleted when the MDB is removed from the server and its durable-subscription-deletion is set to true.

Action:
This is an informational message. No action is needed.

BEA-010216
The Message-Driven EJB: {0} is generating an exception when processing the messages. Delivery failed after {1} attempts. The EJB container will suspend the message delivery for {2} seconds before retry.

Category:
EJB

Cause:
The Message-Driven Bean is generating an exception.

Action:
Check the message delivery methods and resolve the exception condition.

BEA-010221
The Message-Driven EJB: {0} is unable to bind to the JCA resource adapter: {1}. The Error was: {2}

Category:
EJB

Cause:
The JCA resource adapter is not deployed, or the configuration information in the MDB deployment descriptor or corresponding annotation is incorrect.

Action:
Check that the JCA resource adapter is deployed and the configuration information in the MDB deployment descriptor or corresponding annotation is correct.

BEA-010222
The aggregate query {0} has a primitive return type but the query returned null because there were no values to which to apply the aggregate function.

Category:
EJB

Cause:
There were no values to which to apply the aggregate function

Action:
Handle ObjectNotFoundException correctly on the application side.

BEA-010223
EJB deployed Message Driven Bean {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-010224
The EJB Timer: {0} has failed to successfully time out in {1} consecutive attempts. The container will delay the timeout for {2} milliseconds as configured for the timer.

Category:
EJB

Cause:
This was caused by a failed ejbTimeout.

Action:
It is possible that no action needs to be taken. However, it may be good to investigate why the original ejbTimeout failed.

BEA-010225
The EJB Timer: {0} has failed to successfully time out in {1} consecutive attempts. Since no retry delay was configured for this timer, the container will automatically delay the timeout for {2} seconds.

Category:
EJB

Cause:
This was caused by a failed ejbTimeout.

Action:
It is possible that no action needs to be taken. However, it may be good to investigate why the ejbTimeout has consecutively failed.

BEA-010226
Error executing clustered EJB timer for EJB {0} of module {1} of application {2}. While executing, the timer was unable to find a necessary internal resource required to execute. The most likely cause of this issue is that the EJB is no longer configured to use the clustered EJB timer service but timers still exist in the database.

Category:
EJB

Cause:
The most likely cause of this error is that the EJB associated with this timer is no longer configured to use the clustered EJB timer service.

Action:
If the EJB in question is no longer configured to use EJB timers, the timers associated with it should be removed from the database. This can be achieved by re-enabling clustered EJB timers for the EJB and then undeploying the EJB. This will cause any timers associated with the EJB to be removed from the database.

BEA-010227
EJB exception occurred during invocation from home or business: {0} generated exception: {1}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-010228
Failed to update the secondary copy of a stateful session bean business: {0}.

Category:
EJB

Cause:
The server was unable to update the secondary server.

Action:
Check the exception for the exact error message.

BEA-010230
EJB {0} : method name {1} and method name {2} are equal under case-insensitive comparison but both methods have declarative security settings. Declarative security checks are case-insensitive.

Category:
EJB

Cause:
Both of the specified methods have declarative security settings.

Action:
Avoid case-insensitive method name conflicts if method permissions are configured.

BEA-010231
The lock request from EJB {0} with primary key {1} timed-out after waiting {3} ns. The transaction or thread requesting the lock was {2}.

Category:
EJB

Cause:
See error message body.

Action:
See error message body.

BEA-010232
The version of EJB in Module "{0}" is "{1}". However, the deprecated "enable-bean-class-redeploy" feature is not supported in EJB 3.

Category:
EJB

Cause:
See error message body.

Action:
Use the FastSwap feature instead and remove the "enable-bean-class-redeploy" settings in the weblogic-ejb-jar.xml.

BEA-010233
The configuration of "MessagesMaximum" is ignored for non Weblogic JMS.

Category:
EJB

Cause:
See error message body.

Action:
No action is required.

BEA-010234
Failed to unbind {0} from JNDI tree due to {1}.

Category:
EJB

Cause:
See the message body.

Action:
If the application is redeployed, restart the target cluster/server on which the application has been deployed. Please report the issue to My Oracle Support with relevant details.

BEA-010235
The Message-Driven EJB {0} has connected or reconnected to the JCA resource adapter {1}.

Category:
EJB

Cause:
The Message-Driven EJB has been re-associated with the JCA resource adapter.

Action:
No action is required.

BEA-010236
The Message-Driven EJB {0} (status: {1}) has not been associated with the JCA resource adapter, so trying suspending it actually did nothing.

Category:
EJB

Cause:
The Message-Driven EJB has not been associated with the JCA resource adapter, so trying suspending it actually did nothing.

Action:
No action is required.

BEA-010237
The Message-Driven Bean {0} was configured to use a JMS Topic, does not require transactions, and uses a non-WebLogic JMS provider. Only one thread will be used to receive and process all messages.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-010239
EJB container creates a {0} bean with name {1} belonging to {2} module.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-010240
The Message-Driven Bean {0} has connected to JMS destination {1}, but was suspended on its startup because property {2} is set.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-010241
The Message-Driven Bean {0} has connected to Resource Adapter {1}. Property {2} is ignored, because it is not supported by JCA-Based Message-Driven Bean.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011047
In ejb-jar.xml or annotation, EJB {0} has container-transactions set when the EJB has a transaction-type of Bean. The container-transaction settings will be ignored.

Category:
EJB

Cause:
The specified EJB has container-transactions set when the EJB has a transaction-type of Bean.

Action:
No action is required.

BEA-011057
The table {0} was created by the user. The container does not drop or alter user-created tables. The container would verify the table in this case.

Category:
EJB

Cause:
The table was already created by the user.

Action:
Drop the table if the existing table is not correct. The container will then be able to create the table.

BEA-011059
The container was unable to create the DDL file.

Category:
EJB

Cause:
This error does not provide the cause of the error. The log file will contain an exception stack indicating the root cause of the failure.

Action:
Inspect the log file for indications of the root cause of the failure.

BEA-011061
Stack trace associated with message {0} follows:

Category:
EJB

Cause:
An error condition was reported.

Action:
Look for the associated exception in the log or your program to see what the results are. In general, this stack trace will help with debugging an existing problem.

BEA-011062
The following exception has occurred:

Category:
EJB

Cause:
An error condition was reported.

Action:
Review the stack trace, which will help with debugging an existing problem.

BEA-011063
Stateless session beans with bean-managed transactions must commit or roll back their transactions before completing a business method. The method {0} of EJB {1} either returned or generated an Exception without properly completing a transaction.

Category:
EJB

Cause:
A transaction started by the stateless session bean method did not complete before the method completed.

Action:
Check the bean code to determine what caused the transaction to not commit or roll back, and fix code. Pay special attention to any exceptions that may be generated by the method, causing commit or rollback calls to be skipped. Blocks can be used to ensure transactions are properly completed in all situations.

BEA-011070
In the <weblogic-rdbms-bean>, for <ejb-name> {0}, some <field-group>(s) are defined but are not used in any <weblogic-query>, <weblogic-relationship-role> or <relationship-caching> <caching-element>s. The <group-name>(s) of the unreferenced <field-group>(s) are: {1}

Category:
EJB

Cause:
Some field group definitions are not referenced in any query or relationship.

Action:
Remove the field groups listed in the logged message from the descriptor or include its usage appropriately.

BEA-011071
In the <weblogic-rdbms-bean>, for <ejb-name> {0}, some <relationship-caching>(s) are defined but are not used in any <weblogic-query>. The <caching-name>(s) of the unreferenced <relationship-caching>(s) are: {1}

Category:
EJB

Cause:
There are unused relation cachings defined in the weblogic-rdbms descriptor.

Action:
Remove the unused relationship cachings listed in the logged message from the descriptor or include its usage appropriately.

BEA-011073
An error occurred while the EJB container was attempting to obtain information about the table {0} from the database. This information is necessary to validate the mapping between the fields of the EJB {1} and the table. The exception is: {2}

Category:
EJB

Cause:
The most likely cause is an error communicating with the database. The error message should include the specific error message.

Action:
The action depends on the specific error that occurred. Actions may range from retrying the failed deployment to seeking help from your database administrator. Also, ensure that you are using a supported database.

BEA-011076
Unable to deploy the EJB {0} because the database table {1} is not accessible. Ensure that this table exists and is accessible.

Category:
EJB

Cause:
A required database table was not accessible.

Action:
Ensure that the database table exists and is accessible.

BEA-011077
The EJB deployment contains settings for automatically creating or altering database tables. However, the server is in production mode, so no database tables will be created or altered.

Category:
EJB

Cause:
The server is in production mode so the create-default-dbms-tables settings are being ignored.

Action:
No action is required. To suppress the warning, remove the create-default-dbms-tables setting from your EJB deployment.

BEA-011078
An exception occurred while starting the freepool idle timeout timer for ejb: {0}, {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011079
An exception occurred while stopping the freepool idle timeout timer for ejb: {0}, {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011080
An exception occurred while starting the Cache idle timeout timer for cache: {0}, {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011081
An exception occurred while stopping the Cache idle timeout timer for cache: {0}, {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011082
Error: The message-destination-link {0} for the Message-Driven Bean {1} in the application module {2} could not be resolved. The target message-destination for the Message-Driven Bean could not be found. Ensure that the link is correct.

Category:
EJB

Cause:
The target of the message-destination-link could not be found in the application.

Action:
Fix the message-destination-link to point to a valid message-destination.

BEA-011083
The EJB specification prohibits stateful session beans from using the TimerService.

Category:
EJB

Cause:
An illegal call was made to the getTimerService() method on the stateful session beans SessionContext.

Action:
Correct the stateful session bean code so that it does not call the getTimerService() method from the bean class.

BEA-011084
This EJB class does not support EJB timers and therefore is prohibited from using the TimerService. To use EJB timers, the bean class must implement javax.ejb.TimedObject or have a method that is annotated with @Timeout.

Category:
EJB

Cause:
An illegal call to the getTimerService() method on the EJBContext.

Action:
Correct the EJB class so it either implements the javax.ejb.TimedObject interface or ensure that it does not call the getTimerService() method on the EJBContext.

BEA-011085
This timer has either expired or been canceled and therefore cannot be invoked.

Category:
EJB

Cause:
An illegal call to a timer object after the timer had expired or was canceled.

Action:
Ensure your bean class does not invoke expired or canceled timers.

BEA-011086
The timer associated with this TimerHandle has either expired or been canceled.

Category:
EJB

Cause:
The timer associated with the TimerHandle has expired or been canceled.

Action:
No action is required.

BEA-011087
This TimerHandle is being invoked outside of the context of the application in which it was created. Since timers are local objects, they can only be called from within the same application in which they were created.

Category:
EJB

Cause:
This TimerHandle is being invoked outside of the context of the application in which it was created.

Action:
Ensure that your application does not pass any TimerHandle references outside of the scope of the application.

BEA-011088
The following error occurred while invoking the ejbTimeout(javax.ejb.Timer) method of EJB {0}.

Category:
EJB

Cause:
This could be caused by erroneous code in the ejbTimeout method or by the failure of a dependent resource.

Action:
All exceptions that occur while invoking or attempting to invoke the ejbTimeout method should be investigated and resolved. If the ejbTimeout method is non-transactional, that is, has a transaction attribute of NotSupported, or if the bean uses bean-managed transactions, the ejbTimeout method may not be retried, leading to missed timeout notifications.

BEA-011089
The following error occurred while attempting to remove an EJB timer from the persistent store for EJB {0}.

Category:
EJB

Cause:
This is an unexpected error so the cause is unknown. The accompanying exception and stack trace should provide information as to the cause of the error.

Action:
This cause of this error should be investigated and resolved promptly.

BEA-011090
The following error occurred while preparing to invoke the ejbTimeout(javax.ejb.Timer) method of EJB {0}.

Category:
EJB

Cause:
This is an unexpected error so the cause is unknown. The accompanying exception and stack trace should provide information as to the cause of the error.

Action:
All exceptions that occur while attempting to invoke the ejbTimeout method should be investigated and resolved.

BEA-011091
The table {0} cannot be dropped or created since it uses a trigger to update the optimistic column of the EJB. The container will only verify the existence of the table.

Category:
EJB

Cause:
The table uses a trigger to update the optimistic column of the EJB.

Action:
To suppress this warning, set the create-default-dbms-tables value in the RDBMS deployment descriptor to Disabled.

BEA-011092
In production mode, the DropAndCreate, DropAndCreateAlways, and AlterOrCreate options are ignored. The container will only attempt to verify the existence and increment value of the sequence {0}.

Category:
EJB

Cause:
Options that apply only to development mode are ignored in production mode.

Action:
Do not use these values for Automatic Oracle SEQUENCE Generation in production mode.

BEA-011093
The SEQUENCE named {0} with INCREMENT {1} was not found in the database. This SEQUENCE was specified in the CMP deployment descriptor to be used for automatic primary key generation.

Category:
EJB

Cause:
The SEQUENCE was not found.

Action:
Examine the <automatic-key-generation> tag in the CMP deployment descriptor. In particular, re-examine the <generator-name> and verify that this is the correct name of the SEQUENCE.

Also, re-examine the <key-cache-size> and verify that this is the correct size of the SEQUENCE INCREMENT value.

BEA-011094
The SEQUENCE named {0} does not have INCREMENT value of {1} in the database as specified in the CMP deployment descriptor. Either modify the key-cache-value for this SEQUENCE in the deployment descriptor or update the SEQUENCE in the database.

Category:
EJB

Cause:
The SEQUENCE named {0} does not have an INCREMENT value of {1} in the database as specified in the CMP deployment descriptor.

Action:
In the <automatic-key-generation> tag of the CMP deployment descriptor, re-examine the <key-cache-size> and verify that this is the correct size of the SEQUENCE INCREMENT value.

BEA-011095
During EJB deployment, error(s) were encountered while attempting to CREATE the SEQUENCE named {0} with INCREMENT value {1}. {2}

Category:
EJB

Cause:
During EJB deployment, error(s) were encountered while attempting to CREATE the SEQUENCE named {0} with INCREMENT value {1}.

Action:
The message contains the cause of the error. See the message body and resolve the reported error.

BEA-011096
During EJB deployment, error(s) were encountered while setting up The SEQUENCE named {0} with INCREMENT value {1}. {2}

Category:
EJB

Cause:
During EJB deployment, error(s) were encountered while setting up The SEQUENCE named {0} with INCREMENT value {1}.

Action:
The message contains the cause of the error. See the message body and resolve the reported error.

BEA-011097
During EJB deployment, error(s) were encountered while attempting to ALTER the SEQUENCE named {0} with INCREMENT value {1}. {2}

Category:
EJB

Cause:
During EJB deployment, error(s) were encountered while attempting to ALTER the SEQUENCE named {0} with INCREMENT value {1}.

Action:
The message contains the cause of the error. See message body and resolve the reported error.

BEA-011098
No generated primary key was returned from the database insert statement as expected. Verify that the primary key database column for this EJB is an IDENTITY column as declared in the CMP deployment descriptor for this EJB.

Category:
EJB

Cause:
This is most likely caused by a database configuration error. It may also be caused by a JDBC driver that does not support the getGeneratedKeys() method on java.sql.Statement.

Action:
Verify that the primary key column in the database is marked as an IDENTITY column (or a functional equivalent is setup for the column such as a database trigger to insert a value into the primary key column).

BEA-011099
Multiple generated keys were returned from the database insert statement. The EJB container is unable to determine which generated key corresponds to the primary key column. To use the IDENTITY primary key generator, you must only have a single automatically generated database column per EJB.

Category:
EJB

Cause:
This is most likely caused by a database configuration error. Each EJB may only have a single automatically generated database column.

Action:
Verify that the database table corresponding to the EJB only has a single generated column.

BEA-011109
Failed to register JACC policy context handlers for the EJB container.

Category:
EJB

Cause:
An unexpected error condition occurred while registering JACC context policy handlers.

Action:
See the error message stack trace for details on how to resolve this issue.

BEA-011110
The SEQUENCE named {0} has key-cache-size set to {1}, which is less than the INCREMENT_BY value for the sequence in the database. This may generate missing keys.

Category:
EJB

Cause:
The SEQUENCE named {0} has key-cache-size set to {1}, which is less than the INCREMENT_BY value for the sequence in the database.

Action:
In the <automatic-key-generation> tag, re-examine the <key-cache-size> and verify that it is set correctly.

BEA-011111
The SEQUENCE named {0} has key-cache-size set to {1} which is greater than the INCREMENT_BY value for the sequence in the database. This is not allowed as it may generate duplicate keys.

Category:
EJB

Cause:
The key-cache-set size for the SEQUENCE is not valid.

Action:
in the <automatic-key-generation> tag, re-examine the <key-cache-size> and set it to a value less than or equal to the INCREMENT_BY value for the sequence in the database.

BEA-011120
The CMP EJB {0} has enable-batch-operations set to true. The update queries, however, are not suitable for batching. Batched operations are turned off for this batch and the queries will be executed with multiple update statements.

Category:
EJB

Cause:
Batching is turned off for update queries.

Action:
No action is required.

BEA-011121
Error in Message-Driven Bean EJB {0}. The plugin-class {1} could not be found in the server classpath.

Category:
EJB

Cause:
The plugin-class could not be found in the server classpath.

Action:
Add the plugin-class in the server classpath.

BEA-011122
Error in Message-Driven Bean EJB {0}. The plugin-class {1} could not be instantiated.

Category:
EJB

Cause:
The plugin-class could not be instantiated.

Action:
Add the plugin-class in the server classpath.

BEA-011123
Error in Message-Driven Bean EJB {0}. The plugin-class {1} could not be found in the server classpath.

Category:
EJB

Cause:
The plugin-class could not be accessed.

Action:
Add the plugin-class in the server classpath.

BEA-011124
Error in Message-Driven Bean EJB {0}. The plugin-class {1} does not implement weblogic.ejb.spi.SecurityPlugin.

Category:
EJB

Cause:
The plugin-class does not implement weblogic.ejb.spi.SecurityPlugin.

Action:
Make the plugin-class implement weblogic.ejb.spi.SecurityPlugin.

BEA-011125
An unexpected error was encountered while attempting to remove any EJB timers from the persistent store for the EJB {0}.

Category:
EJB

Cause:
An unexpected error occurred while attempting to remove EJB timers from the persistent store.

Action:
See the particular error message for details about the error. If your application is failing to deploy because of this error, it may be necessary to manually remove the timers from the store.

BEA-011126
The same exception has consecutively caused the expiration to fail for EJB timer {0}. Consecutive errors of this type will no longer be logged for the current timer expiration.

Category:
EJB

Cause:
The same exception has consecutively caused expiration of an EJB timer to fail.

Action:
Investigate what caused the ejbTimeout method to fail. The original exception will be logged in a previous error message.

BEA-011127
Error deserializing one or more EJB timers from the persistent store for the EJB deployment {0}. An incompatible change to the class of a Serializable object associated with the timer may be the cause. If this is the case, you can either undeploy your application entirely to remove the EJB timers from the persistent store or revert the incompatible changes to the Serializable class so the EJB timer can be deserialized. The error was: {1}

Category:
EJB

Cause:
A common cause of this error is an incompatible serializable class change in your application.

Action:
If the error is due to an incompatible serializable class change in your application, there are two options for dealing with the serialization errors. The first option is to completely undeploy the EJB. which will cause all of the EJB timers in the persistent store to be permanently removed. The second option is to revert changes to the serializable class that is associated with the EJB timer and redeploy the application. This allows the EJB timer to be deserialized.

BEA-011128
Error creating an instance of the EJB {0}: {1}

Category:
EJB

Cause:
See the reported error message for the cause. This error may be due to a configuration issue or a bug in the EJB container.

Action:
See the specific error message for details and take appropriate action.

BEA-011132
Error deploying EJB {0}. While binding a business interface to the JNDI name {1}, the following error occurred: {2}

Category:
EJB

Cause:
See the specific error for details.

Action:
The action to take depends on the specific error that occurred. If the error was a JNDI naming conflict, you may need to choose a different JNDI name for the interface.

BEA-011135
The EJB {0} is a singleton session bean. EJB 2.1 client views are not supported for singleton session beans.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011136
wasCancelCalled() should only be invoked from within an asynchronous business method invocation with return type Future.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011137
A singleton session bean with bean-managed transactions must commit or roll back a transaction before the business method completes.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011139
The following exception occurred when processing the asynchronous invocation : {0}.

Category:
EJB

Cause:
There error was encountered during the asynchronous invocation.

Action:
See the exception stack trace for details.

BEA-011140
The argument {0} is not a valid local client view for the EJB {1}.

Category:
EJB

Cause:
The argument is not a valid local client view for the EJB.

Action:
Review the EJB configuration and calling code to determine the discrepancy.

BEA-011141
This EJB has already been removed.

Category:
EJB

Cause:
The EJB has already been removed.

Action:
Avoid the call for removed objects.

BEA-011142
Error creating EJB reference: {0}

Category:
EJB

Cause:
An exception occurred while creating an EJB reference.

Action:
The reported exception contains the root cause of the issue. Review the exception to identify the exact problem.

BEA-011143
Error removing stateful session bean: {0}

Category:
EJB

Cause:
An unexpected error occured while trying to remove a stateful session bean.

Action:
The reported exception has the root cause of the issue. Review the exception to identify the actual problem.

BEA-011144
Singleton EJB {0} failed to initialize.

Category:
EJB

Cause:
A singleton EJB {0} failed to initialize.

Action:
The message body has the root cause of the issue. Review it to identify the essential problem.

BEA-011145
Illegal call to a Write method from a Thread holding Read lock.

Category:
EJB

Cause:
An illegal call to a Write method was made

Action:
Remove or rewrite the call.

BEA-011146
Timed out while trying to aquire lock on Singleton {0} to invoke method {1}.

Category:
EJB

Cause:
A timeout occurred while trying to aquire a lock.

Action:
Check Singleton concurrency. A timeout has been reached.

BEA-011147
Singleton {0} is in use by another thread.

Category:
EJB

Cause:
While this Singleton is being invoked, it cannot be called from other threads.

Action:
Check Singleton concurrency.

BEA-011148
Singleton {0} not initialized as Singleton {1} from the DependsOn transitive, closure failed initialization.

Category:
EJB

Cause:
A singleton was not initialized as a Singleton from the DependsOn transitive, closure failed initialization.

Action:
Check the server log for the cause of the dependent Singleton initialization error and resolve it.

BEA-011149
The EJB {0} contains an illegal value for the activation config property MessagesMaximum. The specified value is {1} but the legal values are -1, and 1 through 2^63-1.

Category:
EJB

Cause:
See the error message body.

Action:
Correct the activation config property.

BEA-011151
Unable to determine the {3} to use for Message Driven Bean {0}. Activation Configuration of Message Driven Bean {0} includes conflicting values specified using {1} and {2}. Consider dropping {2} and specifying the intended {3} using property {1}.

Category:
EJB

Cause:
See the error message body.

Action:
See the error message body.

BEA-011152
ConnectionFactoryResourceLink and DestinationResourceLink configuration attributes cannot be mixed with any of the following settings: DestinationJNDIName, InitialContextFactory, ProviderUrl, ConnectionFactoryJNDIName. Ensure that they are mutually exclusive for ejb {0}.

Category:
EJB

Cause:
Conflicting configuration attributes were specified.

Action:
Ensure that these configuration attributes are mutually exclusive.

BEA-011153
EJB {0} has a redundant Activation configuration, property {1} will be used, property {2} can be dropped.

Category:
EJB

Cause:
There is a redundant configuration property.

Action:
See the message body.

BEA-011154
The EJB {0} contains an illegal value for the activation config property TopicMessagePartitionMode. The specified value is {1} but the legal values are Isolated or Shared.

Category:
EJB

Cause:
See the error message body.

Action:
Correct the activation config property.

BEA-011155
Access is denied on a nonexistent method.

Category:
EJB

Cause:
The specified method is not existing.

Action:
Make sure the method is existing.

BEA-011156
Non numeric value was configured for activation config property {0}.

Category:
EJB

Cause:
Non numeric value was configured for activation config property {0}.

Action:
Correct activation config property setting.

BEA-011157
An exception occurred while preparing the EJB module {0}.

Category:
EJB

Cause:
Check the exception for the exact cause.

Action:
Check the exception for the exact error message, and take appropriate action.

BEA-011158
An exception occurred while initializing the EJB module {0}.

Category:
EJB

Cause:
Check the exception for the exact cause.

Action:
Check the exception for the exact error message, and take appropriate action.

BEA-011159
An exception occurred while starting the EJB module {0}.

Category:
EJB

Cause:
Check the exception for the exact cause.

Action:
Check the exception for the exact error message, and take appropriate action.

BEA-011160
The {0} operation has been scheduled for Message-Driven Bean {1} (listening to JMS destination {3}) of application {2}, but error occurred during {0} operation's execution : {4}.

Category:
EJB

Cause:
See the message body.

Action:
Review the reported exception details to identify the exact problem. Correct it and then try again.

BEA-011161
An exception occurred while creating JMS {0} for JMS destination {2} for Message-Driven Bean {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required, as Message-Driven Bean will try recovering from the error. If Message-Driven Bean cannot be recovered, please check and ensure JMS resources are available.

BEA-011162
The Timeout(javax.ejb.Timer) method of EJB {0} cannot be invoked because it was already undeployed.

Category:
EJB

Cause:
This could be caused when EJB is being undeployed or in production redeployment.

Action:
No action is required.

BEA-011223
Cannot invoke stateful callback on {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011224
Unable to bind the interface {0} to {1}. Another EJB has already bound an interface to that name.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011225
Unable to bind the interface {0} to {1}. This EJB has declared another interface already bound to that name.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011226
Error during {0}. Could not get connection: {1} {2}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011227
Error during finder {0}. Exception while preparing query: {1} {2} {3}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011232
Error during finder {0}. Exception while setting parameters for query {1} {2} {3}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011233
Error during finder {0}. Exception while executing query {1} {2}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011234
Could not find an EJB with a field that is mapped to table {0} and column {1}. The SQL query is {2}. Try using an SqlShape annotation to describe the query results or check that the SqlShape annotation in use is correct.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011235
Error in {0}, could not map relationship {1} role {2} to an EJB populated by the query {3}. EJBs populated by this query are: {4}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011236
Error executing finder {0}: SqlShape {1} contains {2} columns, but the result set returned by JDBC contains {3} columns. The number of columns in the SqlShape and the JDBC result set must match.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011237
A stored procedure or function is used by {0}, but no SqlShape is specified.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011238
Error in {0}. SQL query {1} does not select column values for all primary key fields of bean {2}. No columns were selected for the following fields: {3}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011239
Query-caching is not supported for read-write beans.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011240
Error obtaining nativeQuery: {0}, {1}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011241
An attempt was made to do an executeQuery on query {0}, using a non-WebLogic EntityManager.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011242
Internal Error: Extended Persistence Context has been closed!

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011243
attempt at illegal state transaction from {0} to {1}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011244
An illegal call was made to the EJBContext method. getMessageContext can only be called from SLSBs with web-service endpoint interfaces.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011245
The EJB {0} is not an EJB3.0 bean.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011246
The EJB {0} does not declare a {1} home interface.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011247
The EJB {0} does not implement the business interface {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011248
The bean has not been invoked through a business interface.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011249
It is illegal to invoke UserTransaction methods in ejbCreate or the PostConstruct method of a Message-Driven Bean.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011250
It is illegal to invoke UserTransaction methods in ejbRemove or the PreDestroy method of a Message-Driven Bean.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011251
It is illegal to invoke UserTransaction methods in setSessionContext or a dependency injection of a Message-Driven Bean.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011252
It is illegal to invoke UserTransaction methods in setSessionContext or a dependency injection of a stateful session bean.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011253
It is illegal to invoke UserTransaction methods in ejbCreate or the PostConstruct method of a stateless session bean.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011254
It is illegal to invoke UserTransaction methods in ejbRemove or the PreDestroy method of a stateless session bean.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011255
It is illegal to invoke UserTransaction methods in setSessionContext or a dependency injection of a stateless session bean.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011256
Single expiration timers cannot be cancelled from within ejbTimeout.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011257
It is illegal to invoke Timer methods in ejbRemove or a PreDestroy method from asession bean or Message-Driven Bean.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011258
It is illegal to invoke Timer methods in ejbActivate or a PostActivate method.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011259
It is illegal to invoke Timer methods in ejbPassivate or a PrePassivate method.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011260
It is illegal to invoke Timer methods during a dependency injection.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011261
Invocation timed out. Timer is busy.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011262
Error cancelling timer

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011263
EjbJarBean is not set yet.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011264
Method {0} is marked TX_NEVER, but was called within a transaction.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011265
Unexpected exception in afterDelivery(): {0}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011266
An attempt was made to execute getDatabaseProductName using a non-WebLogic EntityManager.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011267
Error calling getDatabaseProductName: {0}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011268
An attempt was made to execute nativeQuery on query {0}, using a non-WebLogic EntityManager.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011269
Error obtaining nativeQuery: {0}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011270
Error preparing query: {0}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011276
An illegal attempt was made to make a re-entrant call to a stateful session bean: {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011277
An illegal attempt was made to make a re-entrant call to a stateful session bean from home: {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-011278
The following dependency that was declared by {0} is not a Singleton Session Bean: {1}.

Category:
EJB

Cause:
A dependency that was specified by a Singleton Session Bean must also be a Singleton Session Bean.

Action:
Remove the illegal dependency from the dependency list or replace it with a Singleton Session Bean.

BEA-011279
The following exception occured in PreDestroy processing for singleton session bean {0}: {1}.

Category:
EJB

Cause:
This is an informational message.

Action:
No action is required.

BEA-012030
Illegal DOCTYPE for a WebLogic RDBMS CMP EJB11 descriptor file. DOCTYPE {0} not permitted. Only DOCTYPE {1} permitted here.

Category:
EJB

Cause:
An illegal DOCTYPE was used.

Action:
Make sure to update appropriate DOCTYPE to the descriptor file.

BEA-012031
The EJB {0} has a finder {1} for which the sql-select-distinct attribute has been specified. This attribute has been deprecated and will not be supported in future releases.

Category:
EJB

Cause:
The deprecated sql-select-distinct attribute was used.

Action:
Use the EJB-QL DISTINCT clause instead. The container will automatically filter duplicates if necessary.

BEA-012032
For EJB {0}, a weblogic-query element in the CMP deployment descriptor has no matching query element in the ejb-jar.xml descriptor. The settings specified in the weblogic-query element will be ignored. The EJB method referred to by the weblogic-query element is {1}.

Category:
EJB

Cause:
The weblogic-query element references a wrong or non-existent query method for this entity EJB.

Action:
Remove the weblogic-query element or update it so that it references the correct query method.

BEA-012033
Compiling generated EJB classes produced the following Java compiler output: {0}

Category:
EJB

Cause:
While compiling EJB generated classes, the Java compiler produced output.

Action:
Typically, there is no action to take. The Java compiler output is printed for informational purposes.

BEA-012035
The Remote interface method: {0} in EJB {1} contains a parameter of type {2} which is not serializable. Though the EJB {1} has call-by-reference set to false, this parameter is not serializable and hence will be passed by reference. A parameter can be passed using call-by-value only if the parameter type is serializable.

Category:
EJB

Cause:
The EJB has call-by-reference set to false. A parameter can be passed using call-by-value only if the parameter type is serializable. As this parameter is not serializable, the parameter will be passed by reference.

Action:
The parameter should implement the java.io.Serializable interface for it to be passed by value.

BEA-012036
Compiling generated EJB classes produced the following Java compiler error message: {0}

Category:
EJB

Cause:
While compiling EJB generated classes, the Java compiler produced output.

Action:
Check for other log messages that give more information about the failure.

BEA-012037
In weblogic-ejb-jar.xml or annotation, a singleton-session-descriptor element was found for EJB {0}. This EJB was not declared as a singleton session bean in ejb-jar.xml or annotation.

Category:
EJB

Cause:
There is an incompatible configuration between weblogic-ejb-jar.xml and ejb-jar.xml.

Action:
Modify weblogic-ejb-jar.xml or ejb-jar.xml to keep configuration consistency whether singleton or non-singleton.

BEA-014000
Problem, encountered illegal value for transaction-isolation {0}.

Category:
EJB

Cause:
See the error message body.

Action:
Specify one of the following legal values: TransactionSerializable, TransactionReadCommitted, TransactionReadCommittedForUpdate, TransactionReadCommittedForUpdateNoWait, TransactionReadUncommitted, or TransactionRepeatableRead.

BEA-014001
RDBMS descriptor {0} contains transaction-isolation settings. These settings may conflict with isolation-level settings in your weblogic-ejb-jar.xml descriptor and will be lost if you edit this descriptor in the console.

Category:
EJB

Cause:
The specified RDBMS descriptor contains transaction-isolation settings.

Action:
Move the isolation-level settings to the weblogic-ejb-jar.xml descriptor.

BEA-014003
EJB {0} uses optimistic concurrency and contains a finder or select method, {1}, for which include-updates is true. This combination of features does not work properly with database {2}.

Category:
EJB

Cause:
Optimistic concurrency is implemented by reading data in a local transaction to avoid holding database locks, unless Oracle is used as the database. Oracle read consistency does not hold read locks, so in this case reads are performed using the current JTA transaction. When reads are performed in a local transaction updates that have been flushed prior to commit of the transaction are not visible.

Action:
Set include-updates for the query to false to avoid this warning message, or if you are using Oracle as your database, set the database-type to Oracle in weblogic-cmp-jar.xml.

BEA-014004
In EJB {0}, <generator-type> is set to {1}. It is incompatible with Batch Operations due to database limitations. Both order-database-operations and enable-batch-operations are turned off by EJB container.

Category:
EJB

Cause:
These are database limitations.

Action:
Turn off automatic-key-generation in order to use batch operations.

BEA-014005
The configured dispatch policy {1} for Message-Driven Bean (MDB) {0} will be ignored: the MDB is not running in a WebLogic thread.

Category:
EJB

Cause:
The queue MDB is driven asynchronously by a non-WebLogic JMS implementation and runs in a non-WebLogic thread mechanism, so the MDBs application thread pool is not configurable.

Action:
To disable this warning, remove the dispatch-policy setting from the MDBs WebLogic descriptor file.

BEA-014006
The Message-Driven Bean (MDB) named {0} has a dispatch policy {1} that refers to an unknown execute queue thread pool. The default execute thread pool will be used instead.

Category:
EJB

Cause:
The specified MDB named has a dispatch policy that refers to an unknown execute queue thread pool.

Action:
Create an execute thread queue pool for the server named {1}, or modify the dispatch-policy attribute in the MDBs WebLogic descriptor file to the name of an already existing execute queue thread pool.

BEA-014007
The bean named {0} contains BLOB or CLOB fields or both, and uses Optimistic Concurrency but no version or timestamp column has been specified. This may result in corruption of BLOB and CLOB data.

Category:
EJB

Cause:
The specified bean contains BLOB or CLOB fields or both, and uses Optimistic Concurrency but no version or timestamp column has been specified.

Action:
Specify "version" or "timestamp" in the <table-map> <verify-columns> element and specify the name of the <version> or <timestamp> column in the <optimistic-column> element.

BEA-014008
In EJB {0}, {1} references an SqlShape element {2} that is not defined. The list of SqlShape elements that are defined for this EJB is: {3}.

Category:
EJB

Cause:
An undefined SqlShape element was referenced.

Action:
Use an existing SqlShape or create the SqlShape that you wish to use.

BEA-014009
The Message-Driven Bean {0} of application {1} will now be suspended, as it listens to global JMS destination {2} and a new application version {3} is being redeployed.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-014010
The Message-Driven Bean {0} of application {1} will now be suspended, as it listens to global JMS topic {2} and a new application version {3} is being redeployed. Note also that the current Message-Driven Bean is not a durable subscriber to the topic, and messages published by the topic after the currently active version of the Message-Driven Bean is suspended may not be received by the new application version.

Category:
EJB

Cause:
The specified Message-Driven Bean listens to the specified global JMS topic and a new application version is being redeployed.

Action:
To ensure that the new application version will receive all messages published while the Message-Driven Bean was suspended, set the activation config property "subscriptionDurability" to "durable" in the deployment descriptor or annotation.

BEA-014011
EJB {0} uses optimistic-concurrency and has the use-select-for-update element in the RDBMS deployment descriptor set to true. This combination of features is incompatible. The use-select-for-update is turned off by the EJB container in this case.

Category:
EJB

Cause:
Optimistic concurrency is implemented by reading data in a local transaction to avoid holding database locks. The element use-select-for-update in the RDBMS deployment descriptor when set to true, will cause SELECT ... FOR UPDATE to be used whenever the bean is loaded from the database, thus locking the table. This conflicts with the Optimistic Concurrency strategy.

Action:
Set use-select-for-update element in the RDBMS deployment descriptor to false to avoid this warning message.

BEA-014012
EJB {0} uses optimistic-concurrency and disables cluster invalidation, but does not have verify-rows set to Read. This combination will prevent detection of stale data if the bean is never modified in a transaction.

Category:
EJB

Cause:
Optimistic concurrency beans verify consistency of data only if the bean has been modified, unless verify-rows is set to Read. If some other member of a cluster modifies a bean, other members will not be notified of this modification and will continue to store stale data unless the other members also attempt to modify the bean.

Action:
Set either of the elements verify-rows to Read or cluster-invalidation-disabled to false in the RDBMS deployment descriptor to avoid this warning message.

BEA-014013
EJB {0} does not have a concurrency-strategy of either optimistic or readOnly and disables cluster invalidation. Cluster invalidation is relevant only for these concurrency strategies.

Category:
EJB

Cause:
When an EJB is using either optimistic or readOnly concurrency-strategy and is deployed to a cluster, the container invalidates such beans on modification to avoid throwing OptimisticConcurrencyExceptions. This invalidation can be turned off by setting the cluster-invalidation-disabled to true in the RDBMS deployment descriptor.

Action:
Set cluster-invalidation-disabled to false in the RDBMS deployment descriptor to avoid this warning message.

BEA-014014
The Message-Driven Bean (MDB) named {0} has a dispatch policy {1} that refers to an unknown work manager. The default work manager will be used instead.

Category:
EJB

Cause:
The specified MDB has a dispatch policy that refers to an unknown work manager.

Action:
Create a work manager for the server named {1}, or modify the dispatch-policy attribute in the MDBs WebLogic descriptor file to the name of an already existing work manager.

BEA-014016
EJB {0} uses readonly-concurrency and has the use-select-for-update element in the RDBMS deployment descriptor set to true. As the bean is read-only, select-for-update is unnecessary.

Category:
EJB

Cause:
Read-only beans cannot be updated. Therefore, use-select-for-update is unnecessary.

Action:
Set use-select-for-update element in the RDBMS deployment descriptor to false to avoid this warning message.

BEA-014017
EJB {0} uses exclusive-concurrency and has the use-select-for-update element in the RDBMS deployment descriptor set to true. As the bean is locked at the server level during a transaction, select-for-update on the database is unnecessary.

Category:
EJB

Cause:
Exclusive concurrency is implemented by locking the bean at the server level when the bean participates in a transaction. Setting the element use-select-for-update in the RDBMS deployment descriptor to true causes SELECT ... FOR UPDATE to be used whenever the

bean is loaded from the database, thus locking the row in the database too. This may be unnecessary, as the bean is locked by the container.

Action:
Set use-select-for-update element in the RDBMS deployment descriptor to false to avoid this warning message.

BEA-014018
EJB {0} uses a verify-columns element in the RDBMS deployment descriptor. This element is applicable only for optimistic concurrency beans. Since this bean does not use optimistic concurrency, this element will be ignored.

Category:
EJB

Cause:
verify-columns is applicable only for optimistic concurrency beans. As the bean does not use optimistic concurrency, this element will be ignored.

Action:
Remove verify-columns element in the RDBMS deployment descriptor to avoid this warning message.

BEA-014019
EJB {0} uses a verify-rows element in the RDBMS deployment descriptor. This element is applicable only for optimistic concurrency beans. Since this bean does not use optimistic concurrency, this element will be ignored.

Category:
EJB

Cause:
verify-rows is applicable only for optimistic concurrency beans. As the bean does not use optimistic concurrency, this element will be ignored.

Action:
Remove the verify-rows element in the RDBMS deployment descriptor to avoid this warning message.

BEA-014020
EJB {0} uses an optimistic-column element in the RDBMS deployment descriptor. This element is applicable only for optimistic concurrency beans. Since this bean does not use optimistic concurrency, this element will be ignored.

Category:
EJB

Cause:
optimistic-column element is applicable only for optimistic concurrency beans. If the bean does not use optimistic concurrency, this element will be ignored.

Action:
Remove the optimistic-column element in the RDBMS deployment descriptor to avoid this warning message.

BEA-014021
The EJB {0} has been successfully deployed. The following remote interfaces have been bound into JNDI with the specified JNDI names:

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-014022
{0} is bound with JNDI name {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015000
The following exception occured while processing annotations: {0}.

Category:
EJB

Cause:
See the exception to determine the cause.

Action:
See the exception to determine the action to take.

BEA-015001
Unable to link class {0} in Jar {1} : {2}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015002
Unable to load class {0} in Jar {1} : {2}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015003
Unable to create virual Jar {0} : {1}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015004
The super class {0} of session bean class {1} is also a session bean class.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015005
The session type is not set in the deployment descriptor or annotation for session bean {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015007
No ejbCreate method was found for init method {0} in bean {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015008
No matching create method for @Init method {0} in bean {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015009
Could not load interceptor class {0}: {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015010
In bean {0}, there are multiple method permission annotations for method {1}, which is illegal.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015011
There are multiple method permission annotations for class {0}, which is illegal.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015012
Unable to load interface class {0}: {1}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015013
Bean class {0} does not implement interface method {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015014
ServiceEndpoint class {0} was specified but cannot be found.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015015
The super class {0} of Message-Driven Bean class {1} is also a Message-Driven Bean class.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015016
Message-Drive Bean {0} does not implement the message listener interface, has no messaging-type specified in the deployment descriptor, or has no messageListenerInterface specified by using @MessageDriven annotation.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015017
In bean class {0}, the @EJB annotation is at class level, so the beanInterface must be explicitly specified.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015018
In interceptor class {0}, the @EJB annotation is at class level, so the beanInterface must be explicitly specified.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015022
{0} is not valid in this context. Bean class: {1}.

Category:
EJB

Cause:
{0} is not valid in this context. Bean class: {1}.

Action:
Remove {0} from the invalid location.

BEA-015023
{0} is not valid in this context. Bean method: {1}.{2}.

Category:
EJB

Cause:
{0} is not valid in this context. Bean method: {1}.{2}.

Action:
Remove {0} annotation from invalid location.

BEA-015024
Could not specify @JNDIName on local business interface {0} of Bean {1}.

Category:
EJB

Cause:
The @JNDIName could not be specified on the local business interface {0} of Bean {1}.

Action:
Remove the annotation from the local business interface.

BEA-015025
Unable to load a class that is specified in your ejb-jar.xml: {0}.

Category:
EJB

Cause:
A class that is specified in your ejb-jar.xml cannot be loaded.

Action:
Check ejb-jar.xml in the EJB JAR file.

BEA-015026
Reference name {0} of @{1} annotation on class {2} is not unique.

Category:
EJB

Cause:
Reference name {0} of @{1} annotation on class {2} is not unique.

Action:
Change the reference name {0} of @{1} annotation on class {2}.

BEA-015027
The Message-Driven EJB is transactional, but the JMS connection factory referenced by the JNDI name {0} is not a JMS XA connection factory.

Category:
EJB

Cause:
The Message-Driven EJB is transactional, but the JMS connection factory referenced by the JNDI name {0} is not a JMS XA connection factory.

Action:
Make the Message-Driven EJB non-transactional, or use a different connection factory that supports XA.

BEA-015028
The EJB {0} contains an illegal value for the activation config property DistributedDestinationConnection. The specified value is {1} but the legal values are EveryMember and LocalOnly.

Category:
EJB

Cause:
See the error message body.

Action:
Correct the activation config property.

BEA-015029
The EJB {0} contains an illegal value for the activation config property TopicMessagesDistributionMode. The specified value is {1} but the legal values are Compatibility, One-Copy-Per-Server, or One-Copy-Per-Application.

Category:
EJB

Cause:
See the error message body.

Action:
Correct the activation config property.

BEA-015030
The EJB {0} has an illegal permutation on distributed topic type and topicMessagesDistributionMode. Replicated distributed topics work with Compatibility, One-Copy-Per-Server, or One-Copy-Per-Application, but partitioned distributed topics only work with One-Copy-Per-Server or One-Copy-Per-Application. The EJB is configured to partitioned distributed topic and Compatibility.

Category:
EJB

Cause:
See the error message body.

Action:
Review the compatibility of distributed topic types and topicMessagesDistributionMode and fix them.

BEA-015031
The EJB {0} has a distributedDestinationConnection configured but the EJB is configured to connect to a remote cluster. Since the distributedDestinationConnection configuration is only valid in a local cluster, the setting will be ignored.

Category:
EJB

Cause:
See the error message body.

Action:
Connect to a local cluster, or remove the distributedDestinationConnection configuration.

BEA-015032
The EJB {0} is configured with the activation config property topicMessagesDistributionMode but the EJB is configured to connect to a JMS Queue. The topicMessagesDistributionMode is valid only for JMS Topic destinations.

Category:
EJB

Cause:
See the error message body.

Action:
Correct the activation config property.

BEA-015033
The EJB {0} has an invalid value configured for the activation config property {1}. Only WebLogic JMS server 10.3.4 or later versions support the values One-Copy-Per-Server or One-Copy-Per-Application. Prior to 10.3.4.0 Weblogic JMS server or other non-Weblogic JMS vendors, only the Compatibility value is supported.

Category:
EJB

Cause:
See the error message body.

Action:
Correct the activation config property.

BEA-015034
This destinaiton {1} is a remote replicated distribution topic which does not support durable subscriptions when the Message-Drive Bean {0} works in Compatibility mode.

Category:
EJB

Cause:
See the error message body.

Action:
Review and fix the compatibility of the activation config property SubscriptionDurability and topicMessagesDistributionMode.

BEA-015035
The EJB {0} is configured to support One-Copy-Per-Server mode but the partitioned topic is configured as LocalOnly. To support One-Copy-Per-Server mode, the LocalOnly setting will be overridden with EveryMember.

Category:
EJB

Cause:
See the error message body.

Action:
Change distributed-destination-connection to EveryMember to remove the warning.

BEA-015036
In the EJB {0}, the value for the activation config property {1} will be ignored since it is overridden with the value {2}.

Category:
EJB

Cause:
See the error message body.

Action:
To remove this warning, remove the duplicated configuration from the activation config property.

BEA-015037
In EJB {0}, the throws clause for method {1} in the bean class contains exceptions that are NOT in the throws clause of the corresponding {2} interface method.

Category:
EJB

Cause:
See the error message body.

Action:
Correct the throws clause. Implementation methods must have all exceptions that are provided by the corresponding interfaces.

BEA-015038
Problems definitively matching up the interface method {0} with a method in the bean class. Please modify your bean class to implement the interface {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015039
Cannot start an inactive Message-Driven Bean {0}. A redployment may be needed.

Category:
EJB

Cause:
See the error message body.

Action:
Redeploy the application and restart it.

BEA-015040
The Message-Driven Bean {0} is inactive now.

Category:
EJB

Cause:
This is an informational message.

Action:
No action is required.

BEA-015041
The Message-Driven Bean {0} is active now.

Category:
EJB

Cause:
This is an informational message.

Action:
No action is required.

BEA-015042
The JNDI name {0} is set for {1} home interface of EJB {2}, but cannot find {1} home in deployment descriptor. Specify {1} home in ejb-jar.xml.

Category:
EJB

Cause:
See the error message body.

Action:
Specify {1} home in ejb-jar.xml.

BEA-015043
A concurrent-call attempt failed on a stateful session bean instance because the lock was held by another thread or transaction, either because concurrent-access is prohibited or access could not be granted in a specific time period. You may change the concurrent-access behavior using the @AccessTimeout annotation or a corresponding element in deployment descriptor.

Category:
EJB

Cause:
See the message detail.

Action:
No action is required.

BEA-015044
@JNDIName is specified on multiple classes for the same business interface {0} but the value is different. Class: {1}; Class: {2}.

Category:
EJB

Cause:
@JNDIName is specified on multiple classes for the same business interface {0} but the value is different. Class: {1}; Class: {2}.

Action:
Remove @JNDIName from either {1} or {2}.

BEA-015045
@JNDIName on the bean implementation class does not provide the class of the client view, but more than one client view exists. Class: {0}.

Category:
EJB

Cause:
@JNDIName on the bean implementation class does not provide the class of the client view, but more than one client view exists. Class: {0}.

Action:
Remove @JNDIName from {0} or provide the class name of each client view.

BEA-015046
Illegal operation, context data is not supported for the Entity Bean.

Category:
EJB

Cause:
An illegal operation has occurred, context data is not supported for the Entity Bean.

Action:
Remove the retrieval operation for the Entity Bean's context data.

BEA-015047
Unable to bind portable JNDI name {0}.

Category:
EJB

Cause:
The portable JNDI name could not be bound. See the exception for the cause.

Action:
Check the exception for the exact error message.

BEA-015048
This EJB class does not have a timeout method. To use TimerService, the bean class must implement javax.ejb.TimedObject or have a method that is annotated with @Timeout.

Category:
EJB

Cause:
You are trying to create a timer but the corresponding EJB does not have a timeout method.

Action:
Correct the EJB class and add a timeout method.

BEA-015049
Interface {0} implemented by EJB class {1} will be treated as a local business interface, because all implemented interfaces by the bean class should be local business interfaces by default. Note that this interface extends java.rmi.Remote exceptionally.

Category:
EJB

Cause:
Interface {0} defaults to be a local business interface but it extends java.rmi.Remote.

Action:
No action is required if the default works for you. If, however, you do want to use {0} as a remote business interface, specify it explicitly using @Remote annoation or deployment descriptor.

BEA-015050
{2} beans with bean-managed transactions must commit or roll back their transactions before completing a lifecycle callback interceptor method. The method {0} of EJB {1} either returned or generated an exception without properly completing a transaction.

Category:
EJB

Cause:
A transaction started by the {2} bean lifecycle callback method did not complete before the method completed.

Action:
Check the bean code to determine what caused the transaction to not commit or roll back and fix the code. Pay special attention to any exceptions that may be generated by the method, causing commit or rollback calls to be skipped. Blocks can be used to ensure transactions are properly completed in all situations.

BEA-015051
The following exception occured in {1} processing for stateful session bean {0}: {2}.

Category:
EJB

Cause:
This is an informational message.

Action:
No action is required.

BEA-015052
Cannot find proper lifecycle callback method {0} in bean class {1} of EJB {2}.

Category:
EJB

Cause:
A lifecycle callback method in bean class must have the signature: "void <METHOD>()"

Action:
Check the bean code to have the correct signature of the lifecycle callback method.

BEA-015054
Error deploying EJB {0}. The JMS connection factory referenced by the JNDI name {0} is a PooledConnectionFactory.

Category:
EJB

Cause:
The JMS connection factory referenced by the JNDI name {0} is a PooledConnectionFactory. For example, the specified JNDI name may be the JNDI name of a resource reference.

Action:
Specify a JMS connection factory JNDI name that, when looked up, does not return a PooledConnectionFactory. For example, specify a JMS connection factory JNDI name that is not the JNDI name of a resource reference.

BEA-015055
Error occurred during full state replication for replica {1} of stateful session bean {0} of resource group {2}: {3}

Category:
EJB

Cause:
The exception was: {3}

Action:
Check the exception for the exact error message.

BEA-015056
Unregistered replicas for stateful session bean {0}

Category:
EJB

Cause:
Unregistered replicas for stateful session bean {0}

Action:
No action required

BEA-015057
An error occurred while attempting to process a message inside a Message-Driven Bean: {0} Exception is : {1}. {2} such exceptions were suppressed in logging.

Category:
EJB

Cause:
This error usually occurs if the onMessage method of the MDB throws an exception.

Action:
Check that the MDB is able to process messages by ensuring that any resources it uses (such as database connections) are available. Check the MDB source code to ensure that it does not have any bugs that cause an exception (such as a NullPointerException) to be generated.

BEA-015058
Error deploying EJB {0}. It references an initial context factory {1} which enables object based security, which is not needed and is not supported by message driven beans.

Category:
EJB

Cause:
Error deploying EJB {0}. It references an initial context factory {1} which enables object based security, which is not needed and is not supported by message driven beans.

Action:
Do not setup MDBs to use an initial context that enables object based security. For example, use a weblogic.jndi.WLInitialContextFactory instead.

BEA-015059
Error deploying EJB {0}. The JMS connection factory with JNDI name {1} is object-based-security enabled and is not supported by MDBs.

Category:
EJB

Cause:
The JMS connection factory with the JNDI name {1} is object-based-security enabled and is not supported by MDBs.

Action:
Do not use object-based-security enabled JMS connection factorys for MDBs.

BEA-015060
Activation exception for stateful session ben {0}: {1}.

Category:
EJB

Cause:
An exception occurred while reading or processing the state of the bean.

Action:
Please check the exception for the exact error message.

BEA-015061
Exception reading the replicated state of stateful session bean {0}: {1}.

Category:
EJB

Cause:
An exception occurred on reading the replicated state of stateful session bean, for example an application upgrade may have introduced a Java serialization incompatibility on the bean state between old and new versions.

Action:
Please check the exception for the exact error message.

BEA-015062
Exception on creating replicated stateful session bean {0}: {1}.

Category:
EJB

Cause:
An exception occurred on creating replicated stateful session bean

Action:
Please check the exception for the exact error message.

BEA-015063
{0} following exceptions were suppressed in logging during a message processing inside Message-Driven Bean. The last occurrence of this exception has a timestamp {1}: {2} Exception is : {3}.

Category:
EJB

Cause:
This can happen if the onMessage method of the MDB consecutively throws exceptions.

Action:
Check that the MDB is able to process messages by ensuring that any resources it uses (such as database connections) are available. Check the MDB source code to ensure that it does not have any bugs that cause an exception (such as a NullPointerException) to be generated.

BEA-015064
An exception occurred in replication for stateful EJB {0} on {1} partition shutting down: {2}

Category:
EJB

Cause:
An exception occurred in replication for stateful EJB {0} on {1} partition shutting down: {2}

Action:
Please check the exception for the exact error message.

BEA-015065
An error occurred on check server or partition state during deactivation of stateful EJB {0}: {1}

Category:
EJB

Cause:
An error occurred on check server or partition state during deactivation of stateful EJB {0}: {1}

Action:
Please check the exception for the exact error message.

BEA-015066
An exception occurred while cleaning up replicas states locally for stateful EJB {0} on {1} partition shutting down: {2}

Category:
EJB

Cause:
An exception occurred while cleaning up replicas states locally for stateful EJB {0} on {1} partition shutting down: {2}

Action:
Please check the exception for the exact error message.

BEA-015067
Ensure bean states are replicated for stateful EJB {0} on {1} partition shutting down

Category:
EJB

Cause:
see message detail

Action:
No action required

BEA-015068
Local replicas clean up for stateful EJB {0} on {1} partition shutting down

Category:
EJB

Cause:
see message detail

Action:
No action required

BEA-015073
Message-Driven Bean {0} is configured with unknown activation-config-property name {1}

Category:
EJB

Cause:
see message detail

Action:
Check if activation-config-property is correct in ejb-jar.xml or annotation.

BEA-015074
The Message-Driven Bean {0} has connected to JMS destination {1} and the MDB is in a suspended state, message processing will start when the MDB is in an active state."

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015075
EJB deployment state {0} for {1}

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015076
EJB module {0} created.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015077
Activated descriptor {0} update for EJB module {1}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015078
The current server is becoming the primary server for replica {1} of EJB {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015079
The current server is becoming the secondary server for replica {1} of EJB {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-015080
The current server is becoming the secondary server for replica {1} of EJB {0}.

Category:
EJB

Cause:
See the message body.

Action:
No action is required.

BEA-040010
JMSServer "{0}" configured {1,choice,0#no session pools|1#1 session pool|2#{1} session pools}.

Category:
JMS

Cause:
This message indicates the number of session pools that were configured or deployed for the JMSServer while processing the configuration file.

Action:
No action is required.

BEA-040014
Failed to start JMSServer. JMS is shutting down.

Category:
JMS

Cause:
The JMS server failed to initialize.

Action:
Modify the configuration and restart the server file. Then reboot the system. There should be earlier messages that indicate the cause of the failure.

BEA-040015
JMS shutdown is complete.

Category:
JMS

Cause:
JMS has been shut down, either at the request of the administrator or due to configuration errors.

Action:
No action is required.

BEA-040017
JMSServer "{0}" connection factory JNDI binding failed, {1}. JMS is shutting down.

Category:
JMS

Cause:
An error was found when binding the connection factory to a JNDI name during configuration.

Action:
Modify the configuration and restart the server file. Then reboot the system.

BEA-040018
Could not obtain a replicated or non-replicated InitialContext from the default provider, {0}.

Category:
JMS

Cause:
An error was encountered when binding a JMS Server to a JNDI name during configuration.

Action:
Modify the configuration and restart the server file. Then reboot the server.

BEA-040019
JMSServer "{0}" failed to bind to JNDI name: {1}.

Category:
JMS

Cause:
An error was encountered when binding a JMS Server to a JNDI name during configuration.

Action:
Modify the configuration and restart the server file. Then reboot the system.

BEA-040024
JMSServer "{0}" byte threshold for destination {1} has been exceeded.

Category:
JMS

Cause:
This is an informational message.

Action:
No action is required.

BEA-040025
JMSServer "{0}" byte threshold condition for destination {1} has cleared.

Category:
JMS

Cause:
This is an informational message.

Action:
No action is required.

BEA-040026
JMSServer "{0}" message threshold for destination {1} has been exceeded.

Category:
JMS

Cause:
This is an informational message.

Action:
No action

BEA-040027
JMSServer "{0}" message threshold condition for destination {1} has cleared.

Category:
JMS

Cause:
This is an informational message.

Action:
No action is required.

BEA-040028
JMSServer "{0}" byte threshold for the server has been exceeded.

Category:
JMS

Cause:
This is an informational message.

Action:
No action is required.

BEA-040029
JMSServer "{0}" byte threshold for server has cleared.

Category:
JMS

Cause:
This is an informational message.

Action:
No action is required.

BEA-040030
JMSServer "{0}" message threshold for the server has been exceeded.

Category:
JMS

Cause:
This is an informational message.

Action:
No action is required.

BEA-040031
JMSServer "{0}" message threshold for the server has cleared.

Category:
JMS

Cause:
This is an informational message.

Action:
No action is required.

BEA-040068
JMSServer "{0}" error occurred while unregistering destination {1}.

Category:
JMS

Cause:
Look for earlier messages that might explain the error.

Action:
Contact My Oracle Support.

BEA-040069
JMSServer "{0}" error occurred while unregistering producer {1}.

Category:
JMS

Cause:
Look for earlier messages that might explain the error.

Action:
Contact My Oracle Support.

BEA-040070
JMSServer "{0}" error occurred while unregistering connection {1}.

Category:
JMS

Cause:
Look for earlier messages that might explain the error.

Action:
Contact My Oracle Support.

BEA-040071
JMSServer "{0}" error occurred while unregistering session {1}.

Category:
JMS

Cause:
Look for earlier messages that might explain the error.

Action:
Contact My Oracle Support.

BEA-040072
JMSServer "{0}" error occurred while unregistering consumer {1}.

Category:
JMS

Cause:
Look for earlier messages that might explain the error.

Action:
Contact My Oracle Support.

BEA-040089
JMSServer "{0}". JMS messages in store ({1}) were migrated from version {2} to 600.

Category:
JMS

Cause:
Message migration happens automatically when starting JMS and an old store exists.

Action:
No action is required.

BEA-040090
Deployed {0,choice,0#no default connection factories|1#1 default connection factory|2#{0} default connection factories}.

Category:
JMS

Cause:
This message indicates the number of default connection factories deployed while processing the configuration file.

Action:
No action is required.

BEA-040095
JMSServer "{0}". Store I/O failure, {1}.

Category:
JMS

Cause:
There is no more of file space, a disk failure occurred, or a database failure occurred.

Action:
Restart the database, if applicable, and restart JMS.

BEA-040107
Undeployed {0,choice,0#no default connection factories|1#1 default connection factory|2#{0} default connection factories}.

Category:
JMS

Cause:
This message indicates the number of default connection factories that were undeployed.

Action:
No action is required.

BEA-040108
User connection factory "{0}" is started.

Category:
JMS

Cause:
The specified user connection factory has been started.

Action:
No action is required.

BEA-040109
JMSServer "{0}" is started.

Category:
JMS

Cause:
The specified JMS Server has been started.

Action:
No action is required.

BEA-040113
JMSServer "{0}", Opening file store "{1}" in directory "{2}". Starting scan of {3,choice,0#0 files|1#1 file|2#{3} files} totaling {4} bytes.

Category:
JMS

Cause:
A JMS server has opened its persistent file store and is about to scan its contents for messages.

Action:
No action is required.

BEA-040119
Failed to deploy a JMS connection factory "{0}" due to {1}.

Category:
JMS

Cause:
The JMS connection factory failed to initialize. Usually this is a configuration error. This may also happen when the server is shutting down but JMS still attempts to create a new connection factory.

Action:
Modify the configuration and restart the server file. Then reboot the system.

BEA-040120
Failed to bind JMS connection factory "{0}" with its JNDI name due to {1}.

Category:
JMS

Cause:
This is a JNDI failure.

Action:
Modify the configuration and restart the server file. Then reboot the system.

BEA-040121
JMSServer "{0}". Cannot be deployed on multiple servers.

Category:
JMS

Cause:
A JMS Server was deployed on more than one WebLogic Server instance, and this is not allowed.

Action:
Change the configuration file and reboot the system.

BEA-040122
Failed to deploy JMS Server "{0}" due to {1}.

Category:
JMS

Cause:
The JMS server failed to initialize. Usually this is a configuration error. This may also happen when the server is shutting down but JMS still attempts to create a new JMS server.

Action:
Modify the configuration and restart the server file. Then reboot the system.

BEA-040123
Failed to start JMS Server "{0}" due to {1}.

Category:
JMS

Cause:
A JNDI failure occurred, or there was a failure when starting destinations, server session pools and/or connection consumers.

Action:
Modify the configuration and restart the server file. Then reboot the system.

BEA-040124
JMSServer "{0}". Failed to create JMS server session pool "{1}" due to {2}.

Category:
JMS

Cause:
The JMS server session pool failed to initialize. Usually this is a configuration error. This may also happen when the server is shutting down but JMS still attempts to create a new JMS server session pool.

Action:
Modify the configuration and restart the server file. Then reboot the system.

BEA-040125
JMSServer "{0}". Failed to create JMS connection consumer "{1}" due to {2}.

Category:
JMS

Cause:
The JMS connection consumer failed to initialize. Usually this is a configuration error. This may also happen when the server is shutting down but JMS still attempts to create a new JMS connection consumer.

Action:
Modify the configuration and restart the server file. Then reboot the system.

BEA-040127
Failed to create JMS multicast socket due to {0}.

Category:
JMS

Cause:
The JMS multicast socket failed to initialize.

Action:
Reboot the system.

BEA-040215
JMS server "{0}". Cannot set "{1}" to -1 when paging is enabled. The value of the attribute remains unchanged.

Category:
JMS

Cause:
This is caused by an invalid configuration.

Action:
Disable paging before setting this value to -1.

BEA-040305
JMS service is initialized and in standby mode.

Category:
JMS

Cause:
The initialization phase of the JMS service is completed and the JMS service is in standby mode.

Action:
No action is required.

BEA-040306
JMS service is active now.

Category:
JMS

Cause:
The activation phase of the JMS service is completed, and the JMS service is in active mode.

Action:
No action is required.

BEA-040307
JMS service is suspending gracefully.

Category:
JMS

Cause:
The JMS service has started the suspension phase. No new work will be accepted and JMS Service will attempt to complete all existing work before it brings itself to standby mode.

Action:
No action is required.

BEA-040308
JMS service is suspending.

Category:
JMS

Cause:
The JMS service has started the suspension phase. No new work will be accepted and all the existing work will be terminated immediately before the JMS service brings itself to standby mode.

Action:
No action is required.

BEA-040321
JMSServer "{0}" is resuming.

Category:
JMS

Cause:
The JMSServer "{0}" is resuming.

Action:
No action is required.

BEA-040324
JMSServer "{0}" is suspending.

Category:
JMS

Cause:
The JMSServer "{0}" is suspending.

Action:
No action is required.

BEA-040325
JMSServer "{0}" is suspended.

Category:
JMS

Cause:
The JMSServer "{0}" is suspended.

Action:
No action is required.

BEA-040351
ExpiredJMSMessage JMSMessageID={0} > {1} {2} </ExpiredJMSMessage

Category:
JMS

Cause:
A message has been expired and the policy is to log the message header fields and messages properties so that they are printed.

Action:
No action is required.

BEA-040352
ExpiredJMSMessage JMSMessageID={0} > {1} </ExpiredJMSMessage

Category:
JMS

Cause:
A message has been expired and the policy is to log the message header fields so that they are printed.

Action:
No action is required.

BEA-040353
ExpiredJMSMessage JMSMessageID={0} > {1} </ExpiredJMSMessage

Category:
JMS

Cause:
A message has been expired and the policy is to log the messages properties so that they are printed.

Action:
No action is required.

BEA-040354
ExpiredJMSMessage JMSMessageID={0} > </ExpiredJMSMessage

Category:
JMS

Cause:
A message has been expired and the policy is to log only the MessageId, or there are no matching message header fields or message properties.

Action:
No action is required.

BEA-040359
Distributed Destination "{0}", member "{1}" is not associated with a physical destination.

Category:
JMS

Cause:
This was caused by a onfiguration error.

Action:
Modify the configuration and restart the server.

BEA-040368
The following exception has occurred:

Category:
JMS

Cause:
An error condition has occurred.

Action:
Look for the associated exception in the log or your program to see what the results are. In general, this stack trace will help in debugging an existing problem.

BEA-040370
Linked Exception ----------

Category:
JMS

Cause:
An error condition was reported.

Action:
No action is required.

BEA-040371
JMSServer "{0}" JMS server session pool is invalid and has not been started "{1}". Exception is "{2}".

Category:
JMS

Cause:
The server session pool is invalid because it has an invalid Connection Factory or Listener.

Action:
Edit the JMS session pool, verify that it has valid attributes, and reboot the server. Alternatively, delete the session pool and add a new valid JMS session pool.

BEA-040372
JMSServer "{0}" error occurred while unregistering the runtime MBean, {1}.

Category:
JMS

Cause:
Unable to contact the Administration Server or unable to find the runtime MBean.

Action:
No action is required.

BEA-040373
Could not find a license for JMS. Please contact Oracle to get a license.

Category:
JMS

Cause:
Unable to get a license for JMS.

Action:
Contact your Oracle sales representative to get a license.

BEA-040376
Destination {0} has been paused for new message production.

Category:
JMS

Cause:
A Production Pause request was issued for the specified destination.

Action:
No action is required.

BEA-040377
Destination {0} has been resumed for new message production.

Category:
JMS

Cause:
A Production Resume request was issued for the specified destination.

Action:
No action is required.

BEA-040378
Destination {0} has been paused for insertion of messages from in-flight work completion.

Category:
JMS

Cause:
An Insertion Pause request was issued for the specified destination.

Action:
No action is required.

BEA-040379
Destination {0} has been resumed for insertion of messages from in-flight work completion.

Category:
JMS

Cause:
An Insertion Resume request was issued for the specified destination.

Action:
No action is required.

BEA-040380
Destination {0} has been paused for consumption.

Category:
JMS

Cause:
A Consumption Pause request has been issued for the specified destination.

Action:
No action is required.

BEA-040381
Destination {0} has been resumed for consumption.

Category:
JMS

Cause:
A Consumption Resume request has been issued for the specified destination.

Action:
No action is required.

BEA-040382
JMSServer {0} has been paused for new message production.

Category:
JMS

Cause:
A Production Pause request was issued for the specified JMSServer.

Action:
No action is required.

BEA-040383
JMSServer {0} has been resumed for new message production.

Category:
JMS

Cause:
A Production Resume request was issued for the specified JMSServer.

Action:
No action is required.

BEA-040384
JMSServer {0} has been paused for insertion of messages from in-flight work completion.

Category:
JMS

Cause:
An Insertion Pause request was issued for the specified JMS server.

Action:
No action is required.

BEA-040385
JMSServer {0} has been resumed for insertion of messages from in-flight work completion.

Category:
JMS

Cause:
An Insertion Resume request has been issued for the specified JMS server.

Action:
No action is required.

BEA-040386
JMSServer {0} has been paused for consumption.

Category:
JMS

Cause:
A Consumption Pause request has been issued for the specified JMS server.

Action:
No action is required.

BEA-040387
JMSServer {0} has been resumed for consumption.

Category:
JMS

Cause:
A Consumption Resume request has been issued for the specified JMS server.

Action:
No action is required.

BEA-040404
Foreign JMS Server "{0}" is started.

Category:
JMS

Cause:
The specified foreign JMS server was started.

Action:
No action is required.

BEA-040405
Failed to bind an entity of Foreign JMS Server "{0}" with their JNDI names due to {1}.

Category:
JMS

Cause:
This was caused by a JNDI failure.

Action:
Modify the JMS module descriptor of the corresponding application and redeploy the application.

BEA-040406
Distributed destination "{0}" is started.

Category:
JMS

Cause:
The specified distributed destination was started.

Action:
No action is required.

BEA-040407
Default connection factory "{0}" with its JNDI name "{1}" is started.

Category:
JMS

Cause:
The specified default connection factory was started.

Action:
No action is required.

BEA-040408
Failed to bind default connection factory "{0}" with its JNDI name "{1}" due to {2}.

Category:
JMS

Cause:
This was caused by a JNDI failure.

Action:
Modify the configuration and restart the server file. Then reboot the system.

BEA-040409
FailedJMSMessage for store-and-forward: JMSMessageID={0} > {1} {2} </FailedJMSMessage

Category:
JMS

Cause:
A message was expired before it was successfully forwarded by the SAF agent, and the policy is to log the message header fields and messages properties so that they are printed.

Action:
No action is required.

BEA-040410
FailedJMSMessage for store-and-forward: JMSMessageID={0} > {1} </FailedJMSMessage

Category:
JMS

Cause:
A message was expired before it was successfully forwarded by the SAF agent, and the policy is to log the message header fields and messages properties so that they are printed.

Action:
No action is required.

BEA-040411
FailedJMSMessage for store-and-forward: JMSMessageID={0} > {1} </FailedJMSMessage

Category:
JMS

Cause:
A message was expired before it was successfully forwarded by the SAF agent, and the policy is to log the message header fields and messages properties so that they are printed.

Action:
No action is required.

BEA-040412
FailedJMSMessage for store-and-forward: JMSMessageID={0} > </FailedJMSMessage

Category:
JMS

Cause:
A message was expired before it was successfully forwarded by the SAF agent, and the policy is to log only the MessageId. Alternatively, there are no matching message header fields or message properties.

Action:
No action is required.

BEA-040420
The JMS transaction branch {1} for destination {0} was administratively committed.

Category:
JMS

Cause:
This was caused by an administrative action.

Action:
No action is required.

BEA-040421
An administrative request to commit the JMS transaction branch {1} on destination {0} failed with the following exception. {2}

Category:
JMS

Cause:
The cause of the failure may be indicated by the exception provided in the error message.

Action:
The transaction may be in an invalid state to allow commit processing. Attempt the operation again or wait for the Transaction Manager to resolve the transaction branch.

BEA-040422
The JMS transaction branch {1} for destination {0} was administratively rolled back.

Category:
JMS

Cause:
This was caused by an administrative action.

Action:
No action is required.

BEA-040423
An administrative request to rollback the JMS transaction branch {1} on destination {0} failed with the following exception. {2}

Category:
JMS

Cause:
The cause of the failure may be indicated by the exception provided in the error message.

Action:
Attempt the operation again or wait for the Transaction Manager to resolve the transaction branch.

BEA-040430
The "UserTransactionsEnabled" attribute on the JMSConnectionFactory "{0}" has been deprecated and replaced by the "XAConnectionFactoryEnabled" attribute. The changes are propagated to/from this new attribute.

Category:
JMS

Cause:
A deprecated attribute was used.

Action:
Use the XAConnectionFactoryEnabled attribute instead.

BEA-040431
The "XAServerEnabled" attribute on the JMSConnectionFactory "{0}" has been deprecated and replaced by the "XAConnectionFactoryEnabled" attribute. The changes are propagated to/from this new attribute.

Category:
JMS

Cause:
A deprecated attribute is used.

Action:
Use the XAConnectionFactoryEnabled attribute instead.

BEA-040442
While attempting to bind JNDI name {0} for destination {1} in module {2}, a JNDI name conflict was found. This destination has not been bound into JNDI.

Category:
JMS

Cause:
Some other entity has already bound this JNDI name globally.

Action:
Determine the owner of the currently bound JNDI name and remove it if it should not be there, or change the JNDI name of this destination so that it does not conflict with the existing one.

BEA-040443
While attempting to change the JNDI name from {0} to {1} for destination {2} in module {3}, a JNDI name conflict was found. This destination is no longer globally bound into JNDI under any name.

Category:
JMS

Cause:
Some other entity has already bound this JNDI name globally.

Action:
Determine the owner the currently bound JNDI name and remove it if it should not be there, or change the JNDI name of this destination so that it does not conflict with the existing one.

BEA-040444
While attempting to unadvertise the JNDI name {0} for destination {1} in module {2}, an error occurred. The name may or may not be unadvertised globally.

Category:
JMS

Cause:
A network connection between the local server and the Administration Server may have gone down.

Action:
Make sure that network connectivity is working properly and that the Administration Server is reachable.

BEA-040445
While attempting to change the JNDI name from {0} to {1} for destination {2} in module {3}, a JNDI name conflict was found. This destination is no longer locally bound into JNDI under any name.

Category:
JMS

Cause:
Some other entity has already bound this JNDI name locally.

Action:
Determine the owner of the currently bound JNDI name and remove it if it should not be there or change the JNDI name of this destination so that it does not conflict with the existing one.

BEA-040446
While attempting to unadvertise the JNDI name {0} for destination {1} in module {2}, an error occurred. The name may or may not be unadvertised locally.

Category:
JMS

Cause:
A network connection between the local server and the Administration Server may have gone down.

Action:
Make sure that network connectivity is working properly and that the Administration Server is reachable.

BEA-040447
While attempting to bind the JNDI name {0} for destination {1} in module {2}, a JNDI name conflict was found. This destination has not been bound into JNDI locally.

Category:
JMS

Cause:
Some other entity has already bound this JNDI name locally.

Action:
Determine the owner of the currently bound JNDI name and remove it if it should not be there, or change the JNDI name of this destination so that it does not conflict with the existing one.

BEA-040448
JMSFileStoreMBean has been deprecated, and has been replaced with FileStoreMBean. The JMSFileStoreMBean "{0}" has been replaced in the configuration with a FileStoreMBean with the same name.

Category:
JMS

Cause:
A deprecated MBean was replaced in the configuration.

Action:
No action is required.

BEA-040449
JMSJDBCStoreMBean has been deprecated, and has been replaced with JDBCStoreMBean. The JMSJDBCStoreMBean "{0}" has been replaced in the configuration with a JDBCStoreMBean with the same name.

Category:
JMS

Cause:
A deprecated MBean was replaced in the configuration.

Action:
No action is required.

BEA-040450
The "PagingStore" attribute on the JMSServerMBean "{0}" has been deprecated. It is being replaced in the configuration with the new "PagingDirectory" attribute.

Category:
JMS

Cause:
A deprecated MBean attribute was replaced in the configuration.

Action:
No action is required.

BEA-040451
The PagingStore attribute on the JMSServerMBean {0} has been deprecated. Since it currently refers to a JMSJDBCStoreMBean, and paging to a JDBC store is not supported, the JMS server will page messages to its local working directory.

Category:
JMS

Cause:
A deprecated MBean attribute was replaced in the configuration.

Action:
No action is required.

BEA-040452
The server session pool feature has been deprecated, and it will be removed in an upcoming release. New applications should use message-driven beans (MDBs) instead.

Category:
JMS

Cause:
A deprecated feature was detected in the configuration.

Action:
Plan to replace use of server session pools in your application.

BEA-040453
The BytesPagingEnabled and MessagesPagingEnabled parmeters on the JMSServer {0} have been deprecated. These parameters are now ignored. The MessageBufferSize parameter should be used to configure paging in this release.

Category:
JMS

Cause:
A deprecated parameter was encountered.

Action:
Plan to use the new MessageBufferSize to control paging.

BEA-040455
Flow control has been enabled on JMS server "{0}" because memory is low

Category:
JMS

Cause:
Too much memory is being used.

Action:
Either increase the amount of memory available to the server, or decrease the MessageBufferSize parameter on the JMS server so that fewer messages remain in memory.

BEA-040456
An entity of type "{3}" with name "{2}" in JMS module "{0}" is not targeted. There is no subdeployment with name "{1}" in the configuration repository (config.xml). Therefore, this entity will not exist anywhere in the domain.

Category:
JMS

Cause:
The entity of the given name and type in the given JMS module does not have a corresponding subdeployment in the configuration repository (config.xml). In order for this entity to exist in the domain, it must be targeted with a sub-deployment element.

Action:
Add a sub-deployment stanza to the appropriate deployment descriptor in config.xml. This will either be a jms-system-resource for a system module, or an app-deployment for a stand-alone JMS deployable module. If the JMS module is inside a Java EE application (an EAR file), then you must add the sub-deployment stanza to the subdeployment that represents this JMS module in the Java EE application. You do not necessarily have to target the subdeployment yet. Simply adding the subdeployment with no targets will remove this warning. However, if you wish for this entity to exist somewhere in your domain you must target the sub-deployment.

BEA-040457
The Template named "{1}" element of Distributed Destination "{0}" is not supported and hence ignored. Please consider using a Uniform Distributed Destination.

Category:
JMS

Cause:
An unsupported attribute JMSTemplate is used in a Distributed Destination.

Action:
Use a Uniform Distributed Destination instead.

BEA-040458
Unable to unprepare {0} in module {1} due to {2}.

Category:
JMS

Cause:
The prepared entity could not unprepare itself in a failure case.

Action:
Refer to the available exception for more information.

BEA-040459
Unable to deactivate {0} in module {1} due to {2}.

Category:
JMS

Cause:
The activated entity could not deactivate itself in a failure case.

Action:
Refer to the available exception for more information.

BEA-040460
Unable to close the JMS component of module {0} due to {1}.

Category:
JMS

Cause:
The JMS component could not close itself.

Action:
Refer to the available exception for more information.

BEA-040461
Unable to deactivate {0} in module {1} due to {2}.

Category:
JMS

Cause:
The activated entity could not deactivate itself in a failure case.

Action:
Refer to the available exception for more information.

BEA-040464
Unable to destroy {0} in module {1} due to {2}.

Category:
JMS

Cause:
The initialized entity could not destroy itself in a failure case.

Action:
More information may be available from the exception.

BEA-040467
Unable to deactivate {0} in module {1} due to {2}.

Category:
JMS

Cause:
The activated entity could not deactivate itself in a failure case.

Action:
More information may be available from the exception.

BEA-040470
Unable to deactivate {0} in module {1} due to {2}.

Category:
JMS

Cause:
The activated entity could not deactivate itself during dynamic deletion.

Action:
More information may be available from the exception.

BEA-040475
The destination {0} does not have an associated quota object. The setting of bytesMaximum to {1} will have no effect.

Category:
JMS

Cause:
Quotas have been reworked. They are no longer hierarchical in nature. Instead, they are objects that can be pointed to explicitly and can be optionally shared between destinations. Hence quotas no longer work as they did in previous releases. When converting from older releases, a decision is made about how to handle quotas based on the setting of the old parameters. These decisions may have been wrong, which would cause this warning to happen.

Action:
Please consider removing this destination from the interop module. Put it in another module. This will allow you to use the new quota features.

BEA-040476
The destination {0} does not have an associated quota object. The setting of messagesMaximum to {1} will have no effect.

Category:
JMS

Cause:
Quotas have been reworked. They are no longer hierarchical in nature. Instead, they are objects that can be pointed to explicitly and can be optionally shared between destinations. Hence quotas no longer work as they did in previous releases. When converting from older releases a decision is made about how to handle quotas based on the setting of the old parameters. These decisions may have been wrong, which would cause this warning to happen.

Action:
Please consider removing this destination from the interop module. Put it in another module. This will allow you to use the new quota features.

BEA-040477
An error occurred while unbinding a remote JNDI object from local JNDI name "{0}". The exception encountered was {1}.

Category:
JMS

Cause:
There may be an error in the JNDI subsystem. See the exception for more information.

Action:
Check the exception message for more detail.

BEA-040478
The JMS subsystem could not deploy or undeploy the default JMS connection factories due to {0}.

Category:
JMS

Cause:
There may be an error in the JNDI subsystem. See the exception for more information.

Action:
Check the exception message for more detail.

BEA-040479
The system failed to roll back an added connection consumer of name {0}. The exception received was {1}.

Category:
JMS

Cause:
See the exception for more information.

Action:
Check the exception message for more detail.

BEA-040480
The system failed to remove a connection consumer of name {0}. The exception received was {1}.

Category:
JMS

Cause:
See the exception for more information.

Action:
Check the exception message for more detail.

BEA-040490
{0} {1} has a conflicting name attribute value, which is now changed to have a unique name with its JMSServer name. The new destination-name attribute now holds the original name value.

Category:
JMS

Cause:
A name conflict has been detected during upgrade for JMS destinations, maybe because in WebLogic Server versions prior to 9.2, more than one destination was allowed to have the same name, as long as the destinations belonged to different JMS servers.

Action:
Ensure that destinations are created with their name decorated with the target JMS server name to avoid conflict.

BEA-040491
A {0} {1} with multiple targets has been split into multiple deployments one for each unique target.

Category:
JMS

Cause:
A JMS Deployment found with multiple unique targets configured.

Action:
In WebLogic Server versions prior to 9.2, both JMSConnectionFactory and ForeignJMSServer were allowed to be targeted to more than one server, cluster, or both. During upgrade of this configuration to WebLogic Server 9.2, these configuration entities are split into more than one entity, one for each unique target.

BEA-040494
An error occurred while shutting down the JMS server {0}: {1}.

Category:
JMS

Cause:
See the detail message.

Action:
The server should still shut down normally. No action is required.

BEA-040496
The template {0} does not have an associated quota object. The setting of bytesMaximum to {1} will have no effect.

Category:
JMS

Cause:
Quotas have been reworked. They are no longer hierarchical in nature. Instead, they are objects that can be pointed to explicitly and can be optionally shared between destinations. Hence quotas no longer work as they did in previous releases. When converting from older releases a decision is made about how to handle quotas based on the setting of the old parameters. These decisions may have been wrong, which would cause this warning to happen.

Action:
Please consider removing this template from the interop module. Put it in another module. This will allow you to use the new quota features.

BEA-040497
The template {0} does not have an associated quota object. The setting of MessagesMaximum to {1} will have no effect.

Category:
JMS

Cause:
Quotas have been reworked. They are no longer hierarchical in nature. Instead, they are objects that can be pointed to explicitly and can be optionally shared between destinations. Hence quotas no longer work as they did in previous releases. When converting from older releases a decision is made about how to handle quotas based on the setting of the old parameters. These decisions may have been wrong, which would cause this warning to happen.

Action:
Consider removing this template from the interop module. Put it in another module. This will allow you to use the new quota features.

BEA-040498
An error occurred while forwarding a message for distributed destination member {0}: {1}

Category:
JMS

Cause:
There may be a temporary network problem, or one of the members of the cluster may be unavailable.

Action:
See the detail message.

BEA-040499
An error occurred while pushing messages to a JMS client: {0}

Category:
JMS

Cause:
There may be a network failure.

Action:
The JMS protocol will recover automatically from such a problem eventually. Check for networking issues or crashed clients.

BEA-040500
Unable to deactivate entity "{0}" in module "{1}" due to {2}.

Category:
JMS

Cause:
The activated entity could not rollback the proposed targeting change.

Action:
More information may be available from the exception.

BEA-040501
Unable to roll back targeting change of the entity "{0}" in module "{1}" due to {2}.

Category:
JMS

Cause:
The changed entity could not roll back in a failure case.

Action:
More information may be available from the exception.

BEA-040502
While attempting to change the targeting of JMS module "{0}", an error occurred while activating the change. The exception returned is: {1}

Category:
JMS

Cause:
The JMS module failed to activate a prepared change during a targeting update.

Action:
More information may be available from the exception.

BEA-040503
The delivery mode override value of destination "{0}" hosted on JMS server "{1}" has been changed from {2} to {3}.

Category:
JMS

Cause:
During the upgrade process, a configuration was detected that would force all messages through the given destination to be non-persistent. Therefore, the upgrade process made that override explicit.

Action:
Review your application code and configuration. If you need a behavior other than the one that the upgrade process chose, you can modify the resulting configuration using the DeliveryMode parameter of the OverridesParams of the destination, or with the HasStore or AllowsPersistentDowngrade parameters of the JMS server on which the destination is targeted.

BEA-040504
While attempting to add an entity with name "{0}", an error occurred while trying to convert the old style entity to the new style entity. The error was "{1}".

Category:
JMS

Cause:
See the description of the exception that occurred for more information on the cause of this failure.

Action:
Take appropriate action based on the determined cause.

BEA-040505
The JMS module named "{0}" inside application "{1}" does not have a sub-deployment stanza named "{0}". Without such a stanza, no entities inside the module will be deployed, since the subdeployments inside of the sub-deployment stanza named "{0}" control where JMS entities inside this module are targeted.

Category:
JMS

Cause:
When a JMS module is inside an EAR file, the targeting information for entities inside that module are nested within a sub-deployment named after the name of the JMS module found in the weblogic-application.xml file of the EAR file. If no sub-deployment exists with the name of the JMS module, then no targeted entities inside the module will become available. This is usually an oversight on the part of the administrator.

Action:
Add a sub-deployment stanza with the name of the JMS module as specified in the weblogic-application.xml file to the app-deployment stanza. Nested inside that sub-deployment, you can target the entities in the module as you normally would.

BEA-040506
The JMS store-and-forward (SAF) forwarder has successfully connected to the remote destination "{0}".

Category:
JMS

Cause:
This is an informational message.

Action:
No action is required.

BEA-040507
The JMS store-and-forward (SAF) forwarder failed to connect to the remote destination "{0}", because of {1}.

Category:
JMS

Cause:
This is either due to a configuration error, a network failure, or the remote destination being temporarily unavailable.

Action:
Check the configuration, network connection, or remote destination.

BEA-040508
BridgeDestinationMBean has been deprecated. The BridgeDestination "{0}" has been replaced in the configuration with a JMSBridgeDestination with the same name.

Category:
JMS

Cause:
A deprecated MBean is being replaced in the configuration.

Action:
No action is required.

BEA-040509
Failed to ${1} JMS Server "{0}" because the earlier attempt to ${2} was failed.

Category:
JMS

Cause:
This error occurred during deployment of the JMS server.

Action:
Fix any deployment errors related to this JMS server.

BEA-040510
While attempting to rename a connection factory named "{0}", an error occurred while attempting to establish a JNDI listener. The cause was {1}.

Category:
JMS

Cause:
There was an error while attempting to establish a JNDI listener. The description of the cause may provide more information about the true cause of the error.

Action:
The cause of this problem may give an indication of the source of this problem. If this problem persists, contact My Oracle Support.

BEA-040511
The system is waiting to unbind connection factory "{0}". An attempt is being made to change the JNDI name of this connection factory from "{1}" to "{2}".

Category:
JMS

Cause:
An attempt is being made to unbind a connection factory from a JNDI name in order to dynamically change the JNDI from one name to another. This message will repeat every twenty seconds for five minutes.

Action:
No action is required.

BEA-040512
An attempt is being made to change the JNDI name of connection factory "{0}" from "{1}" to "{2}". The system has waited to unbind "{1}" for five minutes. The new JNDI name "{2}" may or may not be bound properly.

Category:
JMS

Cause:
The connection factory was not fully unbound after five minutes. Some error may have occurred while attempting to unbind this connection factory.

Action:
In order to maintain the integrity of the connection factory it is recommended you untarget and retarget the connection factory that failed. Otherwise, the connection factory is in an indeterminate state.

BEA-040513
While attempting to rename a connection factory named "{0}", an error occurred while attempting to remove a JNDI listener. The cause was {1}.

Category:
JMS

Cause:
There was an error while attempting to remove a JNDI listener. The description of the cause may provide more information about the true cause of the error.

Action:
The cause of this problem may give an indication of the source of this problem and the action to take. If this problem persists, contact My Oracle Support.

BEA-040514
While attempting to rename a connection factory named "{0}" an error occurred in the JNDI listener. The error was {1}

Category:
JMS

Cause:
While attempting to dynamically change the JNDI name of a connection factory, a JNDI error occurred. The error itself will tell more about the cause of this failure.

Action:
The cause of this problem may give an indication of the source of this problem and the action to take. If this problem persists, contact My Oracle Support.

BEA-040515
A failured occured while attempting to unregister an InterceptionPoint, {0}.

Category:
JMS

Cause:
An exceptoin coccurred while attempting to unregister an InterceptionPoint. The error will provide more details about the cause of this failure.

Action:
The cause of this problem may give an indication of the source of this problem. If this problem persists, contact My Oracle Support.

BEA-040520
One or more Weighted Distributed Destination (WDD) resources were detected in JMS configuration module "{1}": {0}. This resource type was deprecated as of WebLogic Server 10.3.4.0. Consider using a Uniform Distributed Destination (UDD) instead. If you want to suppress this warning, set system property "weblogic.jms.WDD.SuppressDeprecationWarnings" to true when starting each WebLogic Server instance.

Category:
JMS

Cause:
Deprecated resource was used.

Action:
Use the Uniform Distributed Destination instead.

BEA-040521
The JMS resource "{0}" that you are trying to create in module "{1}" is a Weighted Distributed Destination (WDD). This resource type was deprecated as of WebLogic Server 10.3.4.0. Consider using a Uniform Distributed Destination (UDD) instead. If you want to suppress this warning, set system property "weblogic.jms.WDD.SuppressDeprecationWarnings" to true when starting each WebLogic Server instance.

Category:
JMS

Cause:
A deprecated resource is trying to create.

Action:
Use the Uniform Distributed Destination instead.

BEA-040522
Failed to update distributed destination membership in a multi-domain environment: {0}.

Category:
JMS

Cause:
Cross domain security configuration is not properly set up.

Action:
Check the security configuration, especially the cross-domain security configuration if the cross domain security feature is enabled. Contact My Oracle support if the problem persists.

BEA-040523
One or more properties - "{4}", specified by {3} with JNDI name {1} defined in the application {0} deployed to {2} are not recognized by WebLogic Server and are ignored. To change the log level of this message, see the {5} property of {3}.

Category:
JMS

Cause:
One or more properties set for a {3} are not recognized by WebLogic Server.

Action:
If the intent of the application is to specify properties recognized by WebLogic Server, check for a misspelling of the property name(s).

BEA-040524
The subdeployment "{0}" used by an entity of type {1} with name "{2}" in JMS module "{3}" defined in {4}, has no target specified in the configuration repository (config.xml). A subdeployment without a valid target will not be deployed.

Category:
JMS

Cause:
The subdeployment "{0}" is not targeted, so the entity was ignored by the JMS module defined in {4}.

Action:
Specifiy a valid target for the subdeployment "{0}".

BEA-040525
Shut down JMS connections for resource group {0}.

Category:
JMS

Cause:
JMS connections for a resource group were shut down because the resource group has been shut down.

Action:
No action is required.

BEA-040526
JMS Module "{3}" deployed to {4} defines an entity of type {1} with name "{2}" with default targeting enabled. There is no JMS server having a persistent store with distribution policy "{0}" available in {4} to host the entity. The destination "{2}" will be hosted when a JMS server having a persistent store with distribution policy "{0}" is configured in {4}.

Category:
JMS

Cause:
For hosting the entity of type "{1}" with name "{2}" , with default targeting enabled defined in the JMS module "{3}" deployed to {4}, there should be exactly one JMS server with persistent store having distribution policy "{0}" defined in {4}. However, no candidate JMS server was found to host that entity.

Action:
Create a JMS server in {4} with a persistent store having the distribution policy set to "{0}".

BEA-040527
JMS Module "{2}" deployed to {3} defines an entity of type {0} with name "{1}" with default targeting enabled. There is no SAF agent having a persistent store with distribution policy "Distributed" available in {3} to host the entity. The destination "{1}" will be hosted when a SAF agent having a persistent store with distribution policy "Distributed" is configured in {3}.

Category:
JMS

Cause:
For hosting the entity of type "{0}" with name "{1}" , with default targeting enabled defined in the JMS module "{2}" deployed to {3}, there should be exactly one SAF agent with persistent store having distribution policy "Distributed" defined in {3}. However, no candidate SAF agent was found to host that entity.

Action:
Create an SAF agent in {3} with a persistent store having the distribution policy set to "Distributed".

BEA-040528
Start JMS service for partition [{0}]

Category:
JMS

Cause:
The partition is starting up.

Action:
No action is required.

BEA-040529
Shut down JMS service for partition [{0}].

Category:
JMS

Cause:
The partition is shutting down.

Action:
No action is required.

BEA-040530
JMS Destination Definition with JNDI name "{0}" defined in the application "{1}" deployed to {2} will not be hosted as there is no JMS Server having a persistent store with distribution policy "Distributed" available.

Category:
JMS

Cause:
For hosting the JMS destination definition with JNDI name "{0}" defined in the application "{1}" there must be at least one JMS server having a persistent store with distribution policy "Distributed" However, no JMS server is available in {2} to host the JMS destination definition.

Action:
Create a JMS server in {2} with a persistent store having a distribution policy set to "Distributed".

BEA-040531
One or more JMS Servers - "{0}" were not considered to host the entity {3} deployed to "{2} " as they do not have a persistence store with distribution policy set to "{1}".

Category:
JMS

Cause:
The JMS Servers do not have a persistent store with a persistent store set to the indicated value.

Action:
No action is required.

BEA-040532
One or more JMS Servers - "{0}" were not considered to host the destination defined by JMS Destination Definition with JNDI name "{2}" defined in the application "{3}" deployed to {4} as they do not have a persistence store with distribution policy set to "{1}".

Category:
JMS

Cause:
The JMS servers do not have a persistent store with the distribution policy set to the indicated value.

Action:
No action is required.

BEA-040533
The application "{0}" uses a JMS Destination Definition to create a WebLogic JMS {4} with JNDI name "{1}", its generated configuration name is "{3}" and its generated JMS module name is "{2}".

Category:
JMS

Cause:
This is an informational message.

Action:
No action is required.

BEA-040534
Topic "{0}" in module "{1}" has a subscription limit of "{2}" configured.

Category:
JMS

Cause:
This is an informational message.

Action:
No action is required.

BEA-040535
Topic "{0}" in module "{1}" has illegal subscription limit value "{2}" configured via command line system property "{3}". Values must be a positive integer. The limit will be ignored.

Category:
JMS

Cause:
Subscription limit values must be a positive integer.

Action:
Modify system property to specify a legal value and restart the WebLogic server.

BEA-040536
Multiple {1} or/and SAF {1} have been configured with the same name ("{0}") within the same security realm. This potentially may cause those destinations to have the same security policy even if different security policies are specified.

Category:
JMS

Cause:
Potential configuration error.

Action:
Modify the configuration to uniquely name all destinations, including both regular destinations and SAF destinations.

BEA-040537
No more than one {1} or SAF {1} has been configured with the same name ("{0}") within the same security realm. A previously detected warning condition has been cleared.

Category:
JMS

Cause:
This is an informational message.

Action:
No action is required.

BEA-045002
An error occurred while binding the remote JNDI object to the local JNDI name "{0}".

Category:
JMSExceptions

Cause:
The local JNDI name that is attempting to bind to may not be valid.

Action:
Check the JNDI name to see if its syntax is correct.

BEA-045028
The messages threshold for the JMS server {0} has been exceeded for more than one hour.

Category:
JMSExceptions

Cause:
The threshold of the JMS server was exceeded.

Action:
Verify that the messages are being consumed and that sufficient memory is available.

BEA-045029
The messages threshold for the JMS server {0} has been exceeded for more than 90 percent of the running time of the server.

Category:
JMSExceptions

Cause:
The messages threshold of the JMS server was exceeded.

Action:
Verify that the messages are being consumed and that sufficient memory is available.

BEA-045030
The bytes threshold for the JMS server {0} has been exceeded for more than one hour.

Category:
JMSExceptions

Cause:
The bytes threshold of the JMS server was exceeded.

Action:
Verify that the messages are being consumed and that sufficient memory is available.

BEA-045031
The bytes threshold for the JMS server {0} has been exceeded for more than 90 percent of the running time of the server.

Category:
JMSExceptions

Cause:
The bytes threshold of the JMS server was exceeded.

Action:
Verify that the messages are being consumed and that sufficient memory is available.

BEA-045032
While attempting to create destination {1} in module {2} the JMS server {0} could not be found.

Category:
JMSExceptions

Cause:
The JMS server may be shutting down or may not have completed startup.

Action:
Deploy the module again once the JMS server has completed startup.

BEA-045039
An attempt was made to add a JMS entity of an unknown type {1} in the module {0}.

Category:
JMSExceptions

Cause:
The JMS module given to the update was invalid. It contained an unknown type.

Action:
Ensure that the JMS module is valid.

BEA-045040
While attempting to add a {1} named {2} in module {0}, an error occurred.

Category:
JMSExceptions

Cause:
A linked ModuleException will contain more detail about the cause of the failure.

Action:
Examine the linked exception, which will contain more information about the cause of this failure.

BEA-045041
An attempt was made to remove a JMS entity of an unknown type {1} in the module {0}.

Category:
JMSExceptions

Cause:
The JMS module given to the update was invalid. It contained an unknown type.

Action:
Ensure that the JMS module is valid.

BEA-045042
An error occurred while adding {1} to the JMS module {0}.

Category:
JMSExceptions

Cause:
See the linked exception for more detail.

Action:
The linked exception will contain more information about why this add operation failed.

BEA-045043
An error occurred while removing {1} from the JMS module {0}.

Category:
JMSExceptions

Cause:
See the linked exception for more detail.

Action:
The linked exception will contain more information about why this add operation failed.

BEA-045045
A subdeployment named {1} was not found in the module {0}.

Category:
JMSExceptions

Cause:
A subdeployment removal was attempted, but the subdeployment was unknown to the module.

Action:
Contact My Oracle Support.

BEA-045047
The SubDeploymentMBean {0} in deployment {1} can only be targeted to one JMSServerMBean because an entity that can only be targeted to a single JMS server (for example a queue, topic or quota) has a sub-deployment-name element with value {0}

Category:
JMSExceptions

Cause:
The SubDeploymentMBean of the given name cannot be targeted to anything but a single JMS server because an element of the JMS module that points to that subdeployment can only be targeted to a single JMS server.

Action:
Modify the target of the subdeployment so that it only contains a single JMS server.

BEA-045048
The JMS server named {0} has a temporary template configured. The JMSSystemResourceMBean name of the module containing the temporary template is {1}, and the template name is {2}. However, a JMSSystemResourceMBean of name {1} could not be found. The JMS server {0} will not boot until this problem has been fixed.

Category:
JMSExceptions

Cause:
The temporary template for a JMS server must come from a JMSSystemResourceMBean. A common mistake is to put the temporary template into an AppDeployment. However, because the temporary template must be owned by the administrator, all temporary templates must come from JMSSystemResourceMBeans, not AppDeployments.

Action:
Put the temporary template into a JMSSystemResource.

BEA-045049
JMS server {0} does not have a configured temporary template. However an attempt was made to create a temporary destination. This is not allowed.

Category:
JMSExceptions

Cause:
A JMS server without a configured temporary template was used to create a temporary destination. This usage is not allowed.

Action:
Create a JMSSystemResource that contains a template. Use that template as the temporary template for this JMS server.

BEA-045050
A destination named {3} has a jms-create-destination-identifier named {1}. However, another destination named {2} has the same jms-create-destination-identifier. Two destinations with the same jms-create-destination-identifier cannot both be located on the JMS server named {0}.

Category:
JMSExceptions

Cause:
Two destinations cannot both have the same jms-create-destination-identifier on the same JMS server, even if the two destinations are from different modules.

Action:
Either deploy the destination with the offending jms-create-destination-identifier to a different JMS server, or change the value of the jms-create-destination-identifier attribute.

BEA-045051
Two destinations with name {1} were deployed to the JMS server {0}.

Category:
JMSExceptions

Cause:
Two destinations with the same fully qualified name cannot be deployed to the same JMS server. This error should have been caught during the validation phase of the JMS module.

Action:
Contact My Oracle Support.

BEA-045052
An attempt was made to change the target of a JMS entity that cannot have its target changed. The entity has name "{0}". The original target has name "{1}". The proposed target has name "{2}"

Category:
JMSExceptions

Cause:
An attempt was made to change the target of an entity that cannot have its target changed dynamically.

Action:
Untarget a subdeployment and then retarget that subdeployment elsewhere. However, by doing so, the persistent state maintained for entities retargeted in this fashion will not be kept on the old target and may or may not be removed by the system.

BEA-045054
Cannot dynamically add member {1} to sistributed destination {0}.

Category:
JMSExceptions

Cause:
This member has either not been prepared yet or has already been removed.

Action:
Ensure that the distributed destination member is not removed and is in a prepared state.

BEA-045055
Cannot dynamically remove member {1} from distributed destination {0}.

Category:
JMSExceptions

Cause:
This member has either not been activated yet or is an invalid member.

Action:
Ensure that the distributed destination member is valid and is in an activated state.

BEA-045060
The JMS module named "{0}" is neither an AppDeployment nor a JMSSystemResource.

Category:
JMSExceptions

Cause:
An invalid application context was passed to a JMS module.

Action:
Contact My Oracle Support.

BEA-045061
An attempt was made to create a durable subscription on a queue named "{3}". The client identifier is "{0}", the subscriptionName is "{1}" and the selector is "{2}". Durable subscriptions may only be created on topics.

Category:
JMSExceptions

Cause:
An attempt was made to create a durable subscription on a queue.

Action:
Do not attempt to create a durable subscription on a queue.

BEA-045062
There can be no more than one jms-interop-module element in the config.xml file.

Category:
JMSExceptions

Cause:
More than one jms-interop-module element was found in the config.xml file.

Action:
Do not attempt to define more than one jms-interop-module element in the config.xml file.

BEA-045063
The jms-interop-module must have name interop-jms and a descriptor file name jms/interop-jms.xml. This has name "{0}".

Category:
JMSExceptions

Cause:
An attempt was made to use a jms-interop-module with a name other than interop-jms.

Action:
Do not attempt to define a jms-interop-module element in the config.xml file with a name other than interop-jms.

BEA-045064
The target named "{1}" of a JMS module inside a deployment named "{0}" must be a WebLogic Server instance or a cluster. Instead, it is of type "{2}".

Category:
JMSExceptions

Cause:
An attempt was made to target a JMS module to an invalid type of target.

Action:
Do not attempt to target a JMS module to anything other than WebLogic Server instances or clusters. Any other type of target is not understood.

BEA-045065
A JMS module with fully qualified name "{1}" in an application named "{0}" does not have the proper hierarchy of targets. In particular, the subdeployment named "{2}" has a target "{3}" that is not a subtarget of any of the targets of "{0}". For example, the target "{3}" is not a subtarget of "{4}".

Category:
JMSExceptions

Cause:
A target of a subdeployment of a JMS module was not contained within the targets of the whole JMS module.

Action:
Ensure that the JMS module is targeted to a super-set of all the targets of the subdeployment, or retarget the subdeployment within the set of targets for the JMS module.

BEA-045066
The target named "{1}" of a JMS subdeployment named "{3}" inside a deployment named "{0}" must be a JMS server, WebLogic Server instance, or a cluster. Instead, it is of type {2}.

Category:
JMSExceptions

Cause:
An attempt was made to target a JMS subdeployment to an invalid type of target.

Action:
Do not attempt to target a JMS subdeployment to anything other than JMS servers, WebLogic Server instances or clusters. Any other type of target is not understood.

BEA-045067
The field "destination-name" was set to "{3}", in the distributed destination member "{2}", in the distributed destination "{1}", in the module "{0}". The destination-name field of a distributed destination may only be set in the interop module.

Category:
JMSExceptions

Cause:
An attempt was made to set the destination-name field of a distributed destination member type. This is only allowed in the interop module in order to accommodate older clients.

Action:
Change the name of the distributed destination member to the name of the physical queue or topic being referenced, and unset the destination-name field.

BEA-045068
The physical destination named "{3}", in the distributed destination member "{2}", in the distributed destination "{1}", in the module "{0}" does not exist.

Category:
JMSExceptions

Cause:
An attempt was made by a distributed destination member to reference a destination that does not exist. The physical destination referenced to by a distributed destination must already exist.

Action:
Create the physical destination before referring to it, or create the physical destination in the same edit session as the creation of the distributed destination member.

BEA-045069
The JMS module entity named "{2}" of type "{1}" does not exist in the JMSSystemResource "{0}".

Category:
JMSExceptions

Cause:
An attempt was made to reference a JMS module entity that does not exist in the specified JMSSytemResource.

Action:
Create the JMS module entity in the specified JMSSystemResource before referring to it.

BEA-045070
The configuration entity named "{2}" of type "{1}" does not exist in the domain "{0}".

Category:
JMSExceptions

Cause:
An attempt was made to reference a configuration entity that does not exist in the specified domain.

Action:
Create the configuration entity in the specified domain before referring to it.

BEA-045071
The JMS module entity named "{2}" of type "{1}" cannot be created in JMSSystemResource "{0}".

Category:
JMSExceptions

Cause:
The JMS module entity creation using the the JMSModuleHelper API failed. See the accompanying exception for details.

Action:
Resolve the problem identified by the accompanying exception, and retry the operation.

BEA-045072
The configuration entity named "{2}" of type "{1}" cannot be created in domain "{0}".

Category:
JMSExceptions

Cause:
The configuration entity creation using the JMSModuleHelper API failed. See the accompanying exception for details.

Action:
Resolve the problem identified by the accompanying exception, and retry the operation.

BEA-045073
The JMS module entity named "{2}" of type "{1}" cannot be deleted from JMSSystemResource "{0}".

Category:
JMSExceptions

Cause:
The JMS module entity deletion using the JMSModuleHelper API failed. See the accompanying exception for details.

Action:
Resolve the problem identified by the accompanying exception, and retry the operation.

BEA-045074
The configuration entity named "{2}" of type "{1}" cannot be deleted from the domain "{0}".

Category:
JMSExceptions

Cause:
The configuration entity deletion using the JMSModuleHelper API failed. See the accompanying exception for details.

Action:
Resolve the problem identified by the accompanying exception, and retry the operation.

BEA-045075
The JMS module managed entity named "{2}" of type "{1}" cannot be found in the JMSSytemResource "{0}" for modification.

Category:
JMSExceptions

Cause:
The JMS module entity modification using the JMSModuleHelper API failed. See the accompanying exception for details.

Action:
Resolve the problem identified by the accompanying exception, and retry the operation.

BEA-045076
An attempt was made to find and modify a JMS module entity named "{2}", of type "{1}", from the JMSSystemResource "{0}" using a null modifier.

Category:
JMSExceptions

Cause:
The JMSEntityModifier argument for the findAndModifyEntity() helper API cannot be null.

Action:
Use a valid weblogic.jms.extensions.JMSEntityModifer implementation as the modifier argument.

BEA-045077
The destination named "{0}" on the JMS server "{1}" would have caused the JMS server not to boot because the destination StoreEnabled value is true, but the JMS server does not have a store.

Category:
JMSExceptions

Cause:
This configuration does not work in older releases because the destination StoreEnabled value is true, but the JMS server does not have a store.

Action:
Modify the configuration to remove this discrepency, and re-run the upgrade process. Either add a store to the JMS server or change the value of the StoreEnabled parameter on the destination.

BEA-045078
The destination named "{0}" on the JMS server "{1}" has a DeliveryParamsOverrides.DeliveryMode parameter set to persistent, but the JMS server does not have a store.

Category:
JMSExceptions

Cause:
Messages cannot be made persistent on this JMS server because it does not have a store.

Action:
Modify the configuration to remove this discrepency, and re-run the upgrade process. Either add a store to the JMS server or change the value of the DeliveryParamsOverrides.DeliveryMode parameter.

BEA-045079
An attempt was made to send a persistent message to the destination "{0}" hosted on the JMS server "{1}". This JMS server does not have a store, so the quality of service requested is not available.

Category:
JMSExceptions

Cause:
An attempt was made to send a persistent message to a destination hosted by a JMS server that does not have a store. Since the message cannot be persisted, this message cannot be sent at the required quality of service.

Action:
There is a parameter on the JMS server called "AllowsPersistentDowngrade". If this parameter is set to true, then persistent messages sent to this JMS server will be downgraded to non-persistent.

BEA-045080
The flow steps value {1} is larger than the flow interval value {2} in the connection factory "{0}". The flow steps value must be less than or equal to the flow interval value.

Category:
JMSExceptions

Cause:
This is an invalid configuration. The flow steps value must be less than the entire flow interval.

Action:
Modify the configuration of the connection factory to have the flow steps value be less than or equal to the flow interval.

BEA-045081
The SessionsMaximum attribute of a JMSSessionPoolMBean has the bad value {0}. The value should be -1 or a positive integer.

Category:
JMSExceptions

Cause:
This is an invalid configuration.

Action:
Modify the configuration of the JMSSessionPoolMBean.

BEA-045082
An unexpected naming exception occurred while binding the destination "{0}" to the JNDI name "{1}".

Category:
JMSExceptions

Cause:
The naming exception should contain more information about why this operation failed.

Action:
See the attached naming exception message, which should have more information about why this operation failed.

BEA-045083
An unexpected naming exception occurred while binding the destination "{0}" to the JNDI name "{1}" to the local JNDI context.

Category:
JMSExceptions

Cause:
The naming exception should contain more information about why this operation failed.

Action:
See the attached naming exception, which should have more information about why this operation failed.

BEA-045084
An unexpected naming exception occurred while binding the destination "{0}" to the JNDI name "{1}" to the application JNDI context.

Category:
JMSExceptions

Cause:
The naming exception should contain more information about why this operation failed.

Action:
See the attached naming exception, which should have more information about why this operation failed.

BEA-045085
Could not find a license for JMS. Contact Oracle to obtain a license.

Category:
JMSExceptions

Cause:
A license for JMS was not obtained.

Action:
Contact Oracle to obtain a license.

BEA-045086
The jms-system-resource cannot have the name interop-jms.

Category:
JMSExceptions

Cause:
An attempt was made to define a jms-system-resource with the name interop-jms.

Action:
Do not attempt to define a jms-system-resource element in the config.xml file with the name interop-jms.

BEA-045087
The JMS deployment "{0}" has the descriptor file name "{1}", which is reserved for internal use only.

Category:
JMSExceptions

Cause:
An attempt was made to define a JMS deployment with the reserved file name "interop-jms.xml". This name is reserved by the system for use as the interop module.

Action:
Do not attempt to define a JMS deployment with the reserved name "interop-jms.xml" as its file name.

BEA-045088
The JMS module descriptor file "{1}" used by the JMS system resource "{0}" is illegal. Either the descriptor file name does not end with -jms.xml or the descriptor is being used by another JMS system resource in the configuration.

Category:
JMSExceptions

Cause:
An attempt was made to define a JMS system resource with the illegal descriptor file name.

Action:
Do not attempt to define a jms-system-resource element in the config.xml file with the illegal descriptor file name.

BEA-045089
SAF error destination {2} of {1} is targeted to a different subdeployment from {0}.

Category:
JMSExceptions

Cause:
The configuration was invalid.

Action:
Correct the deployment descriptor.

BEA-045090
The error handling {1} configured for {0} does not exist in the module.

Category:
JMSExceptions

Cause:
The configuration was invalid.

Action:
Correct the deployment descriptor.

BEA-045091
One of the target ("{1}") of the subdeployment "{2}" for the imported destinations "{0}" is not a legal target type.

Category:
JMSExceptions

Cause:
The configuration was invalid.

Action:
Correct the configuration.

BEA-045092
Imported destinations "{0}": its subdeployment is targeted to a target ("{1}"), which is a receiving-only SAF agent.

Category:
JMSExceptions

Cause:
The configuration was invalid.

Action:
Correct the configuration.

BEA-045093
A UDQ named "{0}" was found in the JMS interop module. UDQs were not available prior to the 9.0 release of WebLogic Server, and therefore cannot be in the JMS interop module. Create another JMS module and put the UDQ in that module.

Category:
JMSExceptions

Cause:
An invalid entity type was found in the JMS module that handles interoperating clients. This element should be placed into a different JMS module.

Action:
Place the entity into another JMS module, and either deploy that module as a system resource or as a deployable resource.

BEA-045094
A UDT named "{0}" was found in the JMS interop module. UDTs were not available prior to the 9.0 release of WebLogic Server, and therefore cannot be in the JMS interop module. Create another JMS module and put the UDT in that module.

Category:
JMSExceptions

Cause:
An invalid entity type was found in the JMS module that handles interoperating clients. This element should be placed into a different JMS module.

Action:
Place the entity into another JMS module, and either deploy that module as a system resource or as a deployable resource.

BEA-045095
An SAF imported destinanation named "{0}" was found in the JMS interop module. SAF imported destinations were not available prior to the 9.0 release of WebLogic Server, and therefore cannot be in the JMS interop module. Create another JMS module and put the SAF imported destinations in that module.

Category:
JMSExceptions

Cause:
An invalid entity type was found in the JMS module that handles interoperating clients. This element should be placed into a different JMS module.

Action:
Place the entity into another JMS module, and either deploy that module as a system resource or as a deployable resource.

BEA-045096
An SAF remote context named "{0}" was found in the JMS interop module. SAF remote contexts were not available prior to the 9.0 release of WebLogic Server, and therefore cannot be in the JMS interop module. Create another JMS module and put the SAF remote context in that module.

Category:
JMSExceptions

Cause:
An invalid entity type was found in the JMS module that handles interoperating clients. This element should be placed into a different JMS module.

Action:
Place the entity into another JMS module, and either deploy that module as a system resource or as a deployable resource.

BEA-045097
An SAF error handlings named "{0}" was found in the JMS interop module. SAF error handlings were not available prior to the 9.0 release of WebLogic Server, and therefore cannot be in the JMS interop module. Create another JMS module and put the SAF error handlings in that module.

Category:
JMSExceptions

Cause:
An invalid entity type was found in the JMS module that handles interoperating clients. This element should be placed into a different JMS module.

Action:
Place the entity into another JMS module, and either deploy that module as a system resource or as a deployable resource.

BEA-045098
There is a JMS system resource and an application deployment both named "{0}". The names of all JMS system resources and all application deployments must be different.

Category:
JMSExceptions

Cause:
Both a JMS system resource and an application deployment have the same name. This would cause similarly named resources in a JMS module descriptor file to have conflicting runtime names, and therefore is not allowed.

Action:
Change the name of either the JMS system resource or application deployment so that there is no name conflict.

BEA-045099
An attempt was made to create a temporary destination. However, no JMS server in the cluster is able to host temporary destinations. Ensure that at least one of the JMS servers in the cluster has the HostingTemporaryDestinations parameter set to true (which is the default).

Category:
JMSExceptions

Cause:
None of the JMS servers in the cluster are available for hosting temporary destinations.

Action:
Modify the HostingTemporaryDestinations parameter on at least one JMS server in the cluster. Note that in releases prior to 9.0, the default for the ability to host temporary destinations was false, while in 9.0 and beyond, the default for the ability to host temporary destinations is true.

BEA-045100
The createQueue or createTopic call was made with a null or zero length destination name.

Category:
JMSExceptions

Cause:
The createQueue or createTopic call must be made with the name of a destination to find.

Action:
Do not pass a null or zero length string to createQueue or createTopic.

BEA-045101
The destination name passed to the createTopic or createQueue "{0}" is invalid. If the destination name does not contain a "/" character, then it must be the name of a distributed destination that is available in the cluster to which the client is attached. If it does contain a "/" character, then the string before the "/" must be the name of a JMS server or a ".". The string after the "/" is the name of a the desired destination. If the "./" version of the string is used then any destination with the given name on the local WebLogic Server instance will be returned.

Category:
JMSExceptions

Cause:
Either a distributed destination of the given name does not exist in the cluster to which the client is attached or the destination name passed to createTopic or createQueue does not contain a "/" character, or there is nothing before the "/" character.

Action:
Ensure that the distributed destination is available on the same cluster where the client is located, or format the destination name string properly.

BEA-045102
A destination named "{0}" was not found on WebLogic Server instance "{1}".

Category:
JMSExceptions

Cause:
An attempt was made to find a destination of a given name on a particular WebLogic Server instance. No destination of that name could be found on that WebLogic Server instance.

Action:
It is possible that the createTopic or createQueue call was routed to a WebLogic Server instance that does not contain a destination with the given name. The set of WebLogic Server instances where this request can be routed can be controlled by using a connection factory that is only targeted to WebLogic Werver instances that have destinations of the desired name.

BEA-045103
While trying to find a topic or a queue, the specific JMS server requested could not be found. The linked exception may contain more information about the reason for failure.

Category:
JMSExceptions

Cause:
A specific JMS server was requested by a call to createTopic or createQueue. However, the system could not locate the JMS server of that name.

Action:
The WebLogic Server instance on which that JMS server is targeted may be down. The JMS server may be suspended. Check on the status of the JMS server and also on the status of the communication between the servers in the cluster. Check the linked exception for more information about the cause of this failure.

BEA-045104
While trying to find a topic or a queue, the specific JMS server requested could not be found.

Category:
JMSExceptions

Cause:
A specific JMS server was requested by a call to createTopic or createQueue. However, the system could not locate the JMS server of that name.

Action:
Ensure that the JMS server requested exists in the configuration of the cluster to which the client is attached.

BEA-045105
While trying to find a topic or a queue, communication failed with the specific JMS server requested. The linked exception may contain more information about the reason for failure.

Category:
JMSExceptions

Cause:
A specific JMS server was requested by a call to createTopic or createQueue. However, the system could not communicate with the JMS server of that name.

Action:
The WebLogic Server instance on which that JMS server is targeted may be down. The JMS server may be suspended. Check on the status of the JMS server and also on the status of the communication between the servers in the cluster. Check the linked exception for more information about the cause of this failure.

BEA-045106
A destination named "{0}" was found. However, the requested destination was of type "{1}", and the destination found was not of that type.

Category:
JMSExceptions

Cause:
Either the user called createTopic and the destination found was a queue or the user called createQueue and the destination found was a topic.

Action:
Ensure that the destination name requested is of the correct type.

BEA-045107
A communication failure occurred while attempting to remove a durable subscription. The linked exception may contain more details about the cause of the failure.

Category:
JMSExceptions

Cause:
While attempting to remove a durable subscription a communication failure occurred.

Action:
Check on the status of WebLogic Server instance where the destination which the durable subscription refers to resides. Check the linked exception for more information about the cause of this failure.

BEA-045108
The JMS system does not understand request ID {0}.

Category:
JMSExceptions

Cause:
An invalid request ID was presented to the front end manager.

Action:
If this condition persists, contact My Oracle Support.

BEA-045109
A foreign server named "{0}" was found which does not have a connection URL specified. However, it contains a "{2}" named "{1}" that has the same local and remote JNDI name value "{3}". This is an invalid configuration and is not allowed.

Category:
JMSExceptions

Cause:
The user has configured a foreign server without a connection URL and has either a foreign connection factory or a foreign destination with both the local and remote JNDI name matching.

Action:
Ensure that either the foreign server has a connection URL to the foreign server or that the local and remote JNDI names are different.

BEA-045110
The JMS resource named "{0}" has incorrect targeting information. This resource has the default-targeting-enabled attribute set to true and has a valid sub-deployment-name value specified.

Category:
JMSExceptions

Cause:
A JMS resource cannot have both default targeting enabled and a subdeployment name specified.

Action:
Ensure that either the default targeting is enabled or that the valid subdeployment name is specified.

BEA-045111
The JMS resource named "{0}" has incorrect targeting information. A JMS physical destination cannot have the default-targeting-enabled attribute set.

Category:
JMSExceptions

Cause:
A JMS physical destination cannot have the default-targeting-enabled attribute set.

Action:
Ensure that the default-targeting-enabled attribute is not set for the physical destinations.

BEA-045112
The flow minimum value {1} is larger than or equal to the flow maximum value {2} in connection factory "{0}". The flow minimum value must be less than the flow maximum value.

Category:
JMSExceptions

Cause:
This is an invalid configuration. The flow minimum value must be less than the flow maximum value.

Action:
Modify the configuration of the connection factory to have the flow minimum value be less than the flow maximum value.

BEA-045113
JMS distributed destination forward request denied for the destination named "{1}". Reason "{0}".

Category:
JMSExceptions

Cause:
JMS distributed destinations may not have been fully initialized.

Action:
If forwarding does not begin after a few minutes, contact My Oracle Support.

BEA-045114
Failed to unsubscribe the subscription "{0}", client ID "{1}". This connection has a client ID policy of UNRESTRICTED and cannot unsubscribe a durable subscription without a topic object.

Category:
JMSExceptions

Cause:
An attempt was made to unsubscribe a durable subscription using the standard javax.jms.Session.unsubscribe(String name) method from a connection that has a client ID policy of UNRESTRICTED.

Action:
Use the weblogic.jms.extensions.WLSession.unsubscribe(Topic topic, String name) API to unsubscribe a durable subscription from a connection that has a client ID policy of UNRESTRICTED. If using a pre-AS11gR1PS3 Java client, upgrade to a AS11gR1PS3 client. If using a non-Java client, clean up the durable subscription from the Administration Console or use WebLogic Scripting Tool (WLST) commands or scripts.

BEA-045115
The SubDeploymentMBean {0} in JMS Module {1} contains a standalone queue, topic or quota that can only be targeted to a single non-clustered JMS Server or to a clustered JMS Server with Singleton distribution-policy.

Category:
JMSExceptions

Cause:
The SubDeploymentMBean of the given name cannot be targeted to anything but a single non-clustered JMS Server or to a clustered JMS Server with Singleton distribution-policy.

Action:
Modify the target of the subdeployment so that it contains only a single non-clustered JMS Server or a clustered JMS Server with Singleton distribution-policy.

BEA-045116
The Replicated Distributed Topic (RDT) cannot have its members hosted by a cluster targeted JMSServer. The RDT named {0} in JMS Module {2} has its subdeployment {1} targeted to the Clustered JMSServer {3}.

Category:
JMSExceptions

Cause:
The RDT named {0} in JMS Module {2} has its subdeployment {1} targeted to the Clustered JMSServer {3}.

Action:
Modify the target of the subdeployment so that it does not contain a cluster targeted JMSServer.

BEA-045119
The current JMS message is a Unit-of-Order (UOO) or Unit-of-Work (UOW) message that cannot be sent to the distributed destination (DD) "{0}". This DD has its UnitOfOrderRouting attribute configured to "Hash", which does not support UOO/UOW messages when either a DD is configured in a Resource Group scope, or a DD is hosted on a JMS server that is targeted to a cluster. To fix this issue: change the UnitOfOrderRouting attribute to "PathService" and ensure a Path Service is configured and running in the current scope.

Category:
JMSExceptions

Cause:
A Unit-of-Order (UOO) or Unit-of-Work (UOW) JMS message cannot be sent to distributed destinations that have at least one member hosted by a cluster-targeted JMS Server, but the specified Distributed destination has one or more of its members hosted by a cluster-targeted JMS server. The current JMS message is a Unit-of-Order (UOO) or Unit-of-Work (UOW) message that cannot be sent to the distributed destination (DD). This DD has its UnitOfOrderRouting attribute configured to "Hash", which does not support UOO/UOW

messages when either a DD is configured in a Resource Group scope, or a DD is hosted on a JMS server that is targeted to a cluster.

Action:
To fix this issue: change the UnitOfOrderRouting attribute to "PathService" and ensure a Path Service is configured and running in the current scope.

BEA-045120
An injected JMSContext cannot be used when there is neither a transaction nor a valid request scope.

Category:
JMSExceptions

Cause:
An injected JMSContext was used when there is neither a transaction or a valid request scope.

Action:
Change your application so that it only uses an injected JMSContext when there is either a transaction or a valid request scope.

BEA-045121
Exception encountered whilst injecting a JMSContext: unable to create InitialContext: {0}

Category:
JMSExceptions

Cause:
An exception was encountered whilst injecting a JMSContext: unable to create InitialContext: {0}

Action:
Review the cause of the exception, fix the problem and try again.

BEA-045122
Error injecting JMSContext: unable to lookup connection factory with lookup name {0}. The exception was {1}.

Category:
JMSExceptions

Cause:
An error was encountered whilst injecting a JMSContext: unable to lookup connection factory with lookup name {0}. The exception was {1}.

Action:
Review the cause of the exception, fix the problem and try again.

BEA-045123
The method {0} is not permitted on a container-managed (injected) JMSContext.

Category:
JMSExceptions

Cause:
An attempt was made to call the method {0} on a container-managed (injected) JMSContext. The use of this method is not permitted.

Action:
Amend the application so that it does not call methods that are not permitted on a container-managed (injected) JMSContext. Then try again.

BEA-045124
A session mode of SESSION_TRANSACTED is not permitted on a container-managed (injected) JMSContext.

Category:
JMSExceptions

Cause:
An attempt was made to use a container-managed (injected) JMSContext which specified a session mode of SESSION_TRANSACTED. This session mode is not permitted because the JMS specification forbids the use of the commit method on a container-managed (injected) JMSContext.

Action:
Amend the code which declares the injected JMSContext to use a different value of JMSSessionMode, or omit the JMSSessionMode annotation.

BEA-045125
WebLogic JMS extension methods are only available on injected JMSContext objects if the JMS provider being used is WebLogic JMS

Category:
JMSExceptions

Cause:
The application injected a JMSContext for a foreign JMS provider, cast it to weblogic.jms.client.JMSContextInternal and called a method defined on that interface.

Action:
Amend the code to remove the cast to weblogic.jms.client.JMSContextInternal and the call to any methods on that interface.

BEA-045126
WebLogic JMS extension methods are only available on injected JMSContext objects if the JMS provider being used is WebLogic JMS

Category:
JMSExceptions

Cause:
The application injected a JMSContext for a foreign JMS provider, cast it to weblogic.jms.extensions.WLJMSContext and called a method defined on that interface.

Action:
Amend the code to remove the cast to weblogic.jms.extensions.WLJMSContext and the call to any methods on that interface.

BEA-045127
The application "{1}" has defined a resource using {2} Definition with JNDI name "{0}". There is, however, an object already bound to JNDI using that name.

Category:
JMSExceptions

Cause:
The JNDI name used by {1} Definition is already bound to JNDI.

Action:
Define the resource with a different JNDI name.

BEA-045128
The application "{1}" has defined duplicate resources using {2} Definition with JNDI name "{0}", but the duplicate resources defined by the application are not compatible.

Category:
JMSExceptions

Cause:
The application has defined duplicate resources that are not compatible.

Action:
Fix the duplicate resources defined by {2} Definition and redeploy the application.

BEA-045129
{0} in an application.xml and classes outside of a module, is allowed to define a resource only in java:global and java:app namespaces. the application "{1}" has, however, defined a {0} with the name "{2}", which is not valid.

Category:
JMSExceptions

Cause:
An environment entry declared in the application.xml descriptor and classes outside of a module must specify a JNDI name in the namespace java:app or java:global.

Action:
Define the {0} resource in one of the allowed JNDI namespaces.

BEA-045130
The application "{1}" has defined a {0} resource with name "{2}" in a namespace that is not a well-defined namespace by the Java EE specification. The {0} resource is allowed only in one of the JNDI namespaces - java:global, java:app, java:module and java:comp.

Category:
JMSExceptions

Cause:
An invalid JNDI namespace was used to define a {0} resource.

Action:
Define the {0} resource in one of the allowed JNDI namespaces.

BEA-045131
The application "{0}" has specified one or more properties to define a {1} resource. The value set for a property specified by {2} does not, however, match the value expected by WebLogic.

Category:
JMSExceptions

Cause:
The value set for a property does not match the value expected by WebLogic,

Action:
Find the nested exception for more details and correct the configuration.

BEA-045132
The application "{0}" has defined a {1} resource using {2} and specified a property "{3}" with value "{4}", which is not the expected type for that property.

Category:
JMSExceptions

Cause:
An unexpected type was used for the property.

Action:
Check all properties in the defined resource.

BEA-045133
The Uniform Distributed Queue/Topic cannot be hosted by a cluster targeted JMSServer that does not have its distribution-policy set to Distributed. The UDQ/UDT named {0} in JMS Module {2} has its subdeployment {1} targeted to the Clustered JMSServer {3}.

Category:
JMSExceptions

Cause:
The Uniform Distributed Queue/Topic cannot be hosted by a cluster targeted JMSServer that does not have its distribution-policy set to Distributed. The UDQ/UDT named {0} in JMS Module {2} has its subdeployment {1} targeted to the Clustered JMSServer {3}.

Action:
Modify the target of the UDQ/UDT subdeployment so that it is targeted cluster targeted JMSServer with distribution-policy set to Distributed.

BEA-045134
JMS Module "{3}" deployed to {4} defines an entity of type {1} with name "{2}" and with default targeting option enabled. There are more than one JMS servers "{5}", having a persistent store with distribution policy "{0}" available in {4} to host the entity, which is not allowed.

Category:
JMSExceptions

Cause:
For hosting the entity of type {1} with name "{2}" , and with default targeting option enabled defined in the JMS module "{3}" deployed to {4}, there must be exactly one JMS server with persistent store having distribution policy "{0}" defined in "{4}", but more than one candidate JMS servers were found to host that entity.

Action:
Ensure that there is exactly one JMS server with store distribution policy "{0}" defined in scope {4} or use subdeployment to target the entity to the required JMS server.

BEA-045135
JMS Module "{2}" deployed to {3} defines an entity of type {0} with name "{1}" and with default targeting option enabled. There are more than one SAF agents "{4}", having a persistent store with distribution policy "Distributed" available in {3} to host the entity, which is not allowed.

Category:
JMSExceptions

Cause:
For hosting the entity of type "{0}" with name "{1}" , with default targeting enabled defined in the JMS module "{2}" deployed to "{3}", there should be exactly one SAF agent with persistent store having distribution policy "Distributed" defined in "{3}", but more than one candidate SAF agents were found to host that entity.

Action:
Ensure that there is exactly one SAF agent with persistent store having distribution policy "Distributed" defined in scope {3} or use subdeployment to target the entity to the required SAF agent.

BEA-045136
The JMS Server with name "{0}" specified by the property jms-server-name of {1} with JNDI name "{2}" in application {3} is not available in the {4}.

Category:
JMSExceptions

Cause:
The client application has specified a JMS Server with name {0}, which is not available in the {4}.

Action:
If the intent of the application is to target the {5} to a particular JMS Server, specify a valid JMS Server using property jms-server-name.

BEA-045137
Weighted (Non-Uniform) Distributed Destination/Destinations configured under a JMS module "{0}" are not supported because JMS module "{0}" exists under "{1}". Weighted (Non-Uniform) Distributed Destination are not supported in the Resource Group or Resource Group Template scopes.

Category:
JMSExceptions

Cause:
Weighted (Non-Uniform) Distributed Destination/Destinations are not supported under a Resource Group or Resource Group Template scope.

Action:
Correct the configuration.

BEA-045138
A Uniform Distributed Topic "{0}" in JMS module "{1}" is configured with a forwarding policy "Replicated". This policy is unsupported in a Resource Group or Resource Group Template scope and the JMS module "{1}" is configured under "{2}"

Category:
JMSExceptions

Cause:
A Uniform Distributed Topic with forwarding policy "replicated" was used under a Resource Group or Resource Group Template deployment scope.

Action:
Configure the topic to use a "Partitioned" policy or configure a non-distributed topic instead.

BEA-045139
The JMS Server with name "{0}" specified by the property jms-server-name of JMS Destination Definition with JNDI name "{1}" in application {2} has a persistent store with distribution policy "{3}". A JMS Server with a store having distribution policy "Distributed" is only allowed to host the destination defined by JMS Destination Definition.

Category:
JMSExceptions

Cause:
The client application has specified JMS Server with name {0}, having a store with distribution policy {3}, which is not allowed to host a destination defined by a JMS Destination Definition.

Action:
Specify a JMS werver that has distribution policy "Distributed" for property jms-server-name of a JMS Destination Definition.

BEA-045140
Error using a JMSContext object that was injected using @Inject. The JNDI name {0} specified in the @JMSConnectionFactory annotation does not refer to a javax.jms.ConnectionFactory or javax.jms.XAConnectionFactory, it refers to a {1}.

Category:
JMSExceptions

Cause:
An error was encountered while using a JMSContext object that was injected using @Inject. The lookup name {0} specified in the @JMSConnectionFactory annotation does not refer to a javax.jms.ConnectionFactory or javax.jms.XAConnectionFactory, it refers to a {1}.

Action:
Correct the lookup name specified using @JMSConnectionFactory and try again.

BEA-045141
Error using a JMSContext object that was injected using @Inject. Unable to look up the connection factory using the JNDI name {0} that was specified in the @JMSConnectionFactory annotation.

Category:
JMSExceptions

Cause:
An error was encountered while using a JMSContext object that was injected using @Inject. The @JMSConnectionFactory annotation specified that the connection factory to be used could be obtained using the JNDI name (0), but an error occurred while looking up the connection factory.

Action:
Correct the lookup name that was specified using @JMSConnectionFactory and try again.

BEA-045142
WebLogic Server has detected a deprecated JMS Interop Module in your configuration. This feature will be removed in a future release. Oracle recommends that you take appropriate measures to remove dependencies on JMS Interop Modules.

Category:
JMSExceptions

Cause:
A deprecated JMS Interop Module was used in the configuration.

Action:
Remove JMS Interop Modules from the configuration.

BEA-045143
The Subdeployment "{0}" in JMS Module "{1}" contains a standalone Queue or standalone Topic that can only be targeted to the JMS Server/JMS Servers that references a store configured with "Singleton" distribution-policy.

Category:
JMSExceptions

Cause:
A SubDeployment is being referenced by a singleton style resource such as a standalone Queue or standalone Topic, so it must target to the JMS Server/JMS Servers that references a Store configured with "Singleton" distribution-policy. Note that a asubdeployment under a Resource Group or Resource Group Template scope must be targeted to a single JMS Server or to a single SAF Agent.

Action:
Modify the target of the subdeployment so that it contains only JMS server/JMS servers that reference a Store configured with "Singleton" distribution-policy. Note the you must target a subdeployment to single JMS Server or single SAF Agent under a Resource Group or Resource Group Template scope.

BEA-045144
The SubDeployment "{0}" in JMS Module "{1}" contains a Distributed Queue or Distributed Topic that can only be targeted to the JMS Server/JMS Servers that references a Store configured with "Distributed" distribution-policy.

Category:
JMSExceptions

Cause:
The SubDeployment of the given name cannot be targeted to anything but the JMS Server/JMSServers that references a Store that is configured with "Distributed" distribution-policy.

Action:
Modify the target of the subdeployment so that it contains only JMS server/JMS servers that references a Store with "Distributed" distribution-policy. Note the you must target a subdeployment to a single JMS Server or single SAF Agent under a Resource Group or Resource Group Template scope.

BEA-045145
The URL "{0};" references a WebLogic MT partition, but WebLogic JMS Client for Microsoft .NET does not support partitions.

Category:
JMSExceptions

Cause:
WebLogic MT partitions are not supported by WebLogic JMS Client for Microsoft .NET.

Action:
Do not use a partition-scoped url. Use a domain-level provider url instead.

BEA-045146
Destination "{0};" with JNDI name "{1};" is scoped to a WebLogic MT partition, but WebLogic JMS Client for Microsoft .NET do not support partitons.

Category:
JMSExceptions

Cause:
WebLogic MT partitions are not supported by WebLogic JMS Client for Microsoft .NET.

Action:
Do not use a partition-scoped destination. Use a domain-level destination instead.

BEA-045147
ConnectionFactory "{0};" is scoped to a WebLogic MT partition, but WebLogic JMS Client for Microsoft .NET does not support partitons.

Category:
JMSExceptions

Cause:
WebLogic MT partitions are not supported by WebLogic JMS Client for Microsoft .NET.

Action:
Do not use a partition-scoped connection factory. Use a domain-level connection factory instead.

BEA-045148
JMS Destination Definition with JNDI name "{0}" defined in the application "{1}" which is deployed to {2} will not be hosted as there are more than one JMS Servers having a persistent store with distribution policy "Distributed" available.

Category:
JMSExceptions

Cause:
For hosting the JMS Destination Definition with JNDI name "{0}" defined in the application "{1}" there must be at least one JMS server with a persistent store with distribution policy "Distributed" available in {2} to host the JMS destination. More than one JMS servers are available, however, as candidates in {2} to host the destination defined by the JMS Destination Definition.

Action:
Ensure that there is exactly one JMS server available to host the JMS Destination Definition or specify a JMS Server having distribution policy "Distributed" using the property "jms-server-name" to host the destination defined by the JMS Destination Definition on the specified JMS server.

BEA-045149
The application "{0}" has defined a {1} resource with name "{3}" using {2} in an application client module "{4}" and specified a resource adapter "{5}".

Category:
JMSExceptions

Cause:
A {2} in an application client module specifying a resource adapter is not allowed.

Action:
Update the application client module to be compliant.

BEA-045150
The target named "{1}" of an SAF imported destination named "{3}" inside a deployment named "{0}" must be an SAF agent, WebLogic Server instance, or a cluster. Instead, it is of type {2}.

Category:
JMSExceptions

Cause:
An attempt was made to target an SAF imported destination to an invalid type of target.

Action:
Do not attempt to target an SAF imported destination to anything other than JMS servers, ServerMBean or ClusterMBean. Any other type of target is not understood.

BEA-045151
The target named "{1}" of an SAF imported destination named "{3}" inside a deployment named "{0}" must be an SAF agent. Instead, it is of type {2}.

Category:
JMSExceptions

Cause:
An attempt was made to target an SAF imported destination to an invalid type of target.

Action:
Do not attempt to target an SAF imported destination to anything other than JMS servers. Any other type of target is not understood.

BEA-045152
The JMS Module "{1}" deployed to {2} defines a Foreign Server with name "{0}" and is targeted to subdeployment {3}. The subdeployment {3} is, however, targeted to a JMS Server with distribution policy "Singleton", which is not allowed to be used as a target for a Foreign Server.

Category:
JMSExceptions

Cause:
A Foreign Server is not allowed to be targeted to a subdeployment that has a JMS Server with distribution policy "Singleton".

Action:
Change the target of the subdeployment to have a JMS Server with distribution policy "Distributed" used by the Foreign Server or use default targeting.

BEA-045153
The JMS resource with JNDI name "{2}" defined using {0} by the application "{1}" does not have proper hierarchy of targets. "{3}" specified by property jms-server-name is not a subtarget of "{4}".

Category:
JMSExceptions

Cause:
The JMS resource with JNDI name "{2}" defined using {0} by the application "{1}" does not have proper hierarchy of targets. "{3}" specified by property jms-server-name is not a subtarget of "{4}".

Action:
Specify a JMS Server for property jms-server-name which is available in the same hierarchy as that of the application deployment.

BEA-045154
A Uniform Distributed Destination can only be targeted to a JMS Server that is in the same Resource Group or Resource Group Template scope as the uniform distributed destination. JMS Server "{0}" is not in the same scope as the destination.

Category:
JMSExceptions

Cause:
A Uniform Distributed Destination can only be targeted to a JMS Server that is in the same Resource Group or Resource Group Template scope as the uniform distributed destination. JMS Server "{0}" is not in the same scope as the destination.

Action:
Target the Uniform Distributed Destination to JMS Server defined in the same Resource Group/Resource Group Template scope as the uniform distributed destination.

BEA-045155
There is scope conflict. Either a naming context is attached to a pre-12.2.1 WebLogic Server but the scope type is Resource Group or Resource Group Template (the Domain scope type is the only valid type in this case), or a naming context is attached to a partition but the scope type is Domain or a Resource Group Template (the Resource Group scope type is the only supported type in this case).

Category:
JMSExceptions

Cause:
There is scope conflict. Either a naming context is attached to a pre-12.2.1 WebLogic Server but the scope type is Resource Group or Resource Group Template (the Domain scope type is the only valid type in this case), or a naming context is attached to a partition but the scope type is Domain or a Resource Group Template (the Resource Group scope type is the only supported type in this case).

Action:
When accessing resource group template or domain level configuration ensure that the specified naming context is attached to a domain level scope.Also, when accessing either resource group or resource group template configuration, ensure that the naming context is attached to WebLogic 12.2.1 or greater server.

BEA-045156
Could not find partition name in the given "Context" Object.

Category:
JMSExceptions

Cause:
Could not find partition name in the given "Context" Object.

Action:
Verify valid partition name is attached to the "Context" Object.

BEA-045157
{0} named "{1} " does not exist in the {2} scope.

Category:
JMSExceptions

Cause:
{0} named "{1} " does not exist in the {2} scope.

Action:
Specify a {0} which exists for deleting the same.

BEA-045158
A {0} named "{1} " does not exist in the Resource Group or Resource Group Template {2}.

Category:
JMSExceptions

Cause:
A {0} named "{1} " does not exist in the Resource Group or Resource Group Template {2}.

Action:
Specify a {0} which exists.

BEA-045159
A {0} "{1}" does not exist under {2}.

Category:
JMSExceptions

Cause:
A {0} "{1}" does not exist under {2}.

Action:
Specify a correct scope name, partition name and scope type.

BEA-045160
The Target name "{0}" is not allowed in {1} scope. Target name must be null in Resource Group/Resource Group Template scope and It should not be null for Domain scope.

Category:
JMSExceptions

Cause:
The Target name "{0}" is not allowed in {1} scope. Target name must be null in Resource Group/Resource Group Template scope and It should not be null for Domain scope.

Action:
Specify a valid target.

BEA-045161
Parameter {0} can't be null or empty.

Category:
JMSExceptions

Cause:
Parameter {0} can't be null or empty.

Action:
Specify a valid {0}.

BEA-045162
Operation "{0}" cannot be invoked in Resource Group or Resource Group Template scope.

Category:
JMSExceptions

Cause:
Operation "{0}" cannot be invoked in Resource Group or Resource Group Template scope.

Action:
Operation "{0}" is not allowed in current scope. Please verify your configuration.

BEA-045163
Targets of Uniform Distributed Destination deployment overlap. JMS Server named: " {0} " is been identified twice as potential JMSServer for hosting the Uniform Distributed Destionation's members under the Uniform Distributed.

Category:
JMSExceptions

Cause:
Weblogic Internal Error.

Action:
An Uniform Destionation can be targeted to single JMS Server.Please verify the configuration.

BEA-045164
Invalid partition name: the given partition Name {0} does not exist under {1}.

Category:
JMSExceptions

Cause:
Invalid partition name: the given partition Name {0} does not exist under {1}.

Action:
Verify whether partition name exist in given scope {1}.

BEA-045165
Object-based security is enabled on the JMS connection factory with JNDI name "{0}", therefore it can only be used by a 12.2.2.1.0 or later client.

Category:
JMSExceptions

Cause:
Object-based security is enabled on the JMS connection factory with JNDI name "{0}", therefore it can only be used by a 12.2.2.1.0 or later client.

Action:
Use another JMS connection factory whose Security Policy is ThreadBased.

BEA-045166
The InitialContextFactory {0} is not supported by Foreign Server.

Category:
JMSExceptions

Cause:
The InitialContextFactory {0} is not supported by Foreign Server.

Action:
Do not use this InitialContextFactory {0} because it is not supported by Foreign Server.

BEA-045167
The proposed JNDI name {0} for destination {1} is already bound by another object of type {2}. {3}

Category:
JMSExceptions

Cause:
TBD

Action:
TBD

BEA-045168
Connection is closed because {0} is shutting down.

Category:
JMSExceptions

Cause:
The associated ResourceGroup or Partition is coming down.

Action:
No action is required.

BEA-045169
The method "{0}" is not supported in {1} scope. The scope type should be Resource Group.

Category:
JMSExceptions

Cause:
The method "{0}" is not supported in {1} scope. The scope type should be Resource Group.

Action:
Specify a valid scope.

BEA-045170
A JMS module has an incorrectly configured store-and-forward (SAF) error handler named "{0}". The error handler is configured with a "Redirect" error handling policy, and this policy requires an explicitly configured error destination in the error handler, where the error destination must not be the same as any of the destinations that use the error handler.

Category:
JMSExceptions

Cause:
The module configuration was invalid.

Action:
Correct the module configuration.

BEA-050000
{0} is an obsolete property. Use {1} to create the context instead.

Category:
JNDI

Cause:
Property {0} is obsolete. However, this property name can still be used to retrieve the property value.

Action:
Use property {1} instead of {0} in the future.

BEA-050001
WLContext.close() was called in a different thread than the one in which it was created.

Category:
JNDI

Cause:
The threads used to create and close the context are different. As a result, the context entries associated with the creating thread might not be cleaned up.

Action:
Close the context in the creating thread.

BEA-050002
Cannot replicate the object that is bound in the JNDI under the name {0}.

Category:
JNDI

Cause:
A non-serializable object cannot be serialized.

Action:
If the object was not intended to be replicated, set the replicate bindings to false. If the object should be replicated to all nodes in the cluster, ensure that the object is serializable or externalizable.

BEA-050003
Cannot create initial context. Reason: {0}

Category:
JNDI

Cause:
Initial context cannot be created.

Action:
Check the exception in the message body.

BEA-050004
Unable to bind. Reason: {0}

Category:
JNDI

Cause:
This was unable to bind.

Action:
Check the exception in the message body.

BEA-050005
Unable to unbind. Reason: {0}

Category:
JNDI

Cause:
This was unable to unbind.

Action:
Check the exception in the message body.

BEA-050006
An attempt was made to look up the versioned object "{0}" from an external client or another application. This can potentially cause in-flight work of the application version not being tracked properly, and thus, be retired prematurely.

Category:
JNDI

Cause:
An attempt was made to look up the versioned object "{0}" from an external client or another application. This can potentially cause in-flight work of the application version not being tracked properly, and thus, be retired prematurely.

Action:
Ensure that the possibility of premature retirement of the application version is either tolerated or handled properly. To disable this check, set the JNDI environment property as specified by weblogic.jndi.WLContext.ALLOW_EXTERNAL_LOOKUP to "true" when performing lookup of the versioned object.

BEA-050007
An attempt was made to look up the non-versioned global resource "{0}" from an application version "{1}". This can potentially cause conflict of the global resource usages among multiple application versions.

Category:
JNDI

Cause:
An attempt was made to look up the non-versioned global resource "{0}" from an application version "{1}". This can potentially cause conflict of the global resource usages among multiple application versions.

Action:
Ensure that usages of the global resource by multiple application versions do not conflict. To disable this check, set the JNDI environment property as specified by weblogic.jndi.WLContext.ALLOW_GLOBAL_RESOURCE_LOOKUP to "true" when performing lookup of the global resource.

BEA-050008
Illegal cross partition JNDI lookup detected for "{0}" from source context "{1}" to destination context "{2}".

Category:
JNDI

Cause:
An attempt was made to access the "{0}", the current partition is "{1}" but the target partition is "{2}". This cross partition should be taken care of by visibility control.

Action:
Either configure "{0}" to allow cross partition access or modify the application to avoid cross partition lookup. For example, you can use a remote (host:port) url to target the destination.

BEA-055001
Invalid time-to-deliver, must be >= -1

Category:
JMSClientExceptions

Cause:
The time-to-deliver parameter passed to setTimeToDeliver was invalid.

Action:
Change the code to pass a time-to-deliver parameter that is >= -1.

BEA-055002
Cannot convert {0} to a boolean.

Category:
JMSClientExceptions

Cause:
An object that was not null, not a boolean, and not a string could not be converted to a boolean value.

Action:
Ensure that the object passed in is either a boolean or a string.

BEA-055003
Cannot convert null to a byte.

Category:
JMSClientExceptions

Cause:
The null object cannot be converted to a byte value

Action:
Avoid passing null where a byte value is expected

BEA-055004
Cannot convert {0} to a byte.

Category:
JMSClientExceptions

Cause:
An object that was not null, not a byte, and not a string could not be converted to a byte value

Action:
Ensure that the object passed in is either a byte or a string.

BEA-055005
Cannot convert null to a short.

Category:
JMSClientExceptions

Cause:
The null object cannot be converted to a short value.

Action:
Avoid passing null where a short value is expected.

BEA-055006
Cannot convert {0} to a short.

Category:
JMSClientExceptions

Cause:
An object that was not null, not a short, and not a string could not be converted to a short value.

Action:
Ensure that the object passed in is either a short or a string.

BEA-055007
Could not serialize object.

Category:
JMSClientExceptions

Cause:
An object could not be serialized. The linked exception may contain more details.

Action:
See the linked exception which may contain more details.

BEA-055008
Invalid RedeliveryLimit, must be >= -1.

Category:
JMSClientExceptions

Cause:
The RedeliveryLimit parameter passed to setRedeliveryLimit was invalid.

Action:
Change the code to pass a RedeliveryLimit parameter that is >= -1.

BEA-055009
Invalid SendTimeout, must be >= 0

Category:
JMSClientExceptions

Cause:
The SendTimeout parameter passed to setSendTimeout was invalid.

Action:
Change the code to pass a SendTimeout parameter that is >= 0.

BEA-055014
Error sending message

Category:
JMSClientExceptions

Cause:
The linked exception will contain more details concerning the failure to send the message.

Action:
The action will depend on the error that occurred. More information about the specific error that occurred can be found in the linked exception.

BEA-055015
Invalid DeliveryMode

Category:
JMSClientExceptions

Cause:
The DeliveryMode parameter passed to setDeliveryMode was invalid.

Action:
Change the code to pass a valid DeliveryMode value.

BEA-055016
Invalid Priority

Category:
JMSClientExceptions

Cause:
The Priority parameter passed to setPriority was invalid.

Action:
Change the code to pass a valid Priority value.

BEA-055017
Durable connection consumers are not supported.

Category:
JMSClientExceptions

Cause:
The system does not support durable connection consumers.

Action:
Do not attempt to create a durable connection consumer.

BEA-055018
QueueSessions do not support multicast.

Category:
JMSClientExceptions

Cause:
The MULTICAST_NO_ACKNOWLEDGE flag was set in createQueueSession.

Action:
Do not use MULTICAST_NO_ACKNOWLEDGE when creating a QueueSession.

BEA-055019
Duplicate session

Category:
JMSClientExceptions

Cause:
The cause is unknown.

Action:
Contact My Oracle Support.

BEA-055021
ClientID is null

Category:
JMSClientExceptions

Cause:
ClientID is null in a call to setClientID.

Action:
Do not use null in a call to setClientID.

BEA-055022
Zero length clientID

Category:
JMSClientExceptions

Cause:
The clientID passed to setClientID was zero length.

Action:
The clientID must not be zero length.

BEA-055023
Invalid value for messagesMaximum, {0}

Category:
JMSClientExceptions

Cause:
The value given for messagesMaximum in createConnectionConsumer is invalid.

Action:
Change the code to pass a valid messagesMaximum value.

BEA-055024
No such method {0}

Category:
JMSClientExceptions

Cause:
The given method identification number does not exist.

Action:
Check for other log messages that give more information about the failure.

BEA-055025
Invalid messagesMaximum value

Category:
JMSClientExceptions

Cause:
The messagesMaximum parameter passed to setMessagesMaximum was invalid.

Action:
Change the code to pass a valid messagesMaximum value.

BEA-055026
Invalid overrunPolicy value, {0}

Category:
JMSClientExceptions

Cause:
The overrun policy passed to setOverrunPolicy is invalid.

Action:
Change the code to pass a valid overrun policy value.

BEA-055027
Invalid redelivery delay, must be >= -1

Category:
JMSClientExceptions

Cause:
The redeliveryDelay parameter passed to setRedeliveryDelay was invalid.

Action:
Change the code to pass a valid redeliveryDelay value.

BEA-055028
Name must not be null.

Category:
JMSClientExceptions

Cause:
The name parameter passed to createDurableSubscriber was null.

Action:
Change the code to pass a valid name to createDurableSubscriber.

BEA-055029
Name must not be an empty string.

Category:
JMSClientExceptions

Cause:
The name parameter passed to createDurableSubscriber had a length of zero.

Action:
Change the code to pass a valid name to createDurableSubscriber.

BEA-055030
This topic does not support durable subscriptions.

Category:
JMSClientExceptions

Cause:
Durable subscribers are not supported on Distributed Topics and no subscribers at all are supported on SAF topics

Action:
Avoid attempting to create a durable subscriber on a distributed topic or do not create a subscriber on an SAF topic.

BEA-055031
This connection does not have a clientID.

Category:
JMSClientExceptions

Cause:
Unsubscribe was called on a connection without a clientID.

Action:
Avoid attempting to unsubscribe a connection with no clientID

BEA-055032
An attempt was made to create a named consumer ({0}) on a connection with no clientID.

Category:
JMSClientExceptions

Cause:
An attempt was made to create a named consumer on a connection with no clientID.

Action:
Avoid attempting to create a named consumer on a connection with no clientID.

BEA-055033
Queues do not support multicast.

Category:
JMSClientExceptions

Cause:
Queues do not support multicast.

Action:
Avoid attempting to create a multicast consumer on a queue

BEA-055034
Topic {0} does not support multicast.

Category:
JMSClientExceptions

Cause:
An attempt was made to create a multicast consumer on a topic that does not support multicast.

Action:
Avoid attempting to create a multicast consumer on the given topic.

BEA-055035
Cannot open multicast socket, {0}.

Category:
JMSClientExceptions

Cause:
An attempt was made to open a multicast socket and failed. The reason for the failure may be in the exception

Action:
For more details, check the printed exception on the failure to open the multicast socket.

BEA-055036
Cannot join multicast group ({0}) {1}

Category:
JMSClientExceptions

Cause:
An attempt was made to join a multicast group and failed. The reason for failure may be in the exception.

Action:
For more details, check the printed exception on the failure to join the multicast group.

BEA-055037
Subscription {0} is in use.

Category:
JMSClientExceptions

Cause:
Two subscriptions with the same name are not allowed.

Action:
Avoid attempting to use a subscription name more than once. If necessary, unsubscribe the previous subscription

BEA-055038
An unexpected response ({0}) was received from the server.

Category:
JMSClientExceptions

Cause:
An internal protocol error has occurred.

Action:
Contact My Oracle Support.

BEA-055039
A system error has occurred. The error is {0}.

Category:
JMSClientExceptions

Cause:
The cause of this error may be contained in the printed exception.

Action:
The action will depend on the error that has occurred. Contact My Oracle Support.

BEA-055040
Subscription {0} is in use.

Category:
JMSClientExceptions

Cause:
An attempt was made to remove the named subscription while the subscription was in use.

Action:
Avoid attempting to remove a subscription that is currently in use.

BEA-055041
Cannot leave multicast group ({0}) {1}

Category:
JMSClientExceptions

Cause:
An attempt was made to leave a multicast group and failed. The reason for failure may be in the exception.

Action:
For more details, check the printed exception on the failure to leave the multicast group.

BEA-055042
No such method {0} for class {1}.

Category:
JMSClientExceptions

Cause:
The given method number could not be found in the given class.

Action:
Check for other log messages that give more information about the failure.

BEA-055043
No such method {0} for class {1}.

Category:
JMSClientExceptions

Cause:
The given method number could not be found in the given class.

Action:
Check for other log messages that give more information about the failure.

BEA-055044
Multicast sessions do not support synchronous receives.

Category:
JMSClientExceptions

Cause:
An attempt was made to do a synchronous receive on a multicast consumer.

Action:
Avoid attempting to make a synchronous receive with a multicast consumer.

BEA-055045
An invalid value ({0}) for timeout was specified.

Category:
JMSClientExceptions

Cause:
The timeout given to a receive call is invalid. Timeout values must be positive.

Action:
Change the code so that it does not pass a negative number into a receive call.

BEA-055046
A listener already exists.

Category:
JMSClientExceptions

Cause:
A call to receive cannot be made if the consumer already has a listener.

Action:
Avoid attempting to call receive if a listener already exists for the consumer.

BEA-055047
No such method {0}

Category:
JMSClientExceptions

Cause:
The given method identification number does not exist.

Action:
Check for other log messages that give more information about the failure.

BEA-055048
Multicast selectors are not supported in the thin client.

Category:
JMSClientExceptions

Cause:
Multicast selectors are not supported in the thin client.

Action:
If selectors are required, avoid using the JMS thin client. If selectors are not required, avoid using them while using the thin client.

BEA-055049
An error occurred. See {0}.

Category:
JMSClientExceptions

Cause:
See the message body.

Action:
Check for other log messages that give more information about the failure.

BEA-055050
An error occurred {0}

Category:
JMSClientExceptions

Cause:
See the message body.

Action:
Check for other log messages that give more information about the failure.

BEA-055051
An error occurred {0}

Category:
JMSClientExceptions

Cause:
See the message body.

Action:
Check for other log messages that give more information about the failure.

BEA-055052
Invalid selector {0}

Category:
JMSClientExceptions

Cause:
An error occurred while parsing a selector. The printed exception should have more detail.

Action:
The course of action will depend on the nature of the error. Use a well-formed selector.

BEA-055053
Error creating connection to the server: {0}.

Category:
JMSClientExceptions

Cause:
The printed exception may have information regarding the cause of this failure.

Action:
The course of action will depend on the error printed out in the exception.

BEA-055054
Error finding dispatcher: {0}.

Category:
JMSClientExceptions

Cause:
See the message body.

Action:
Check for other log messages that give more information about the failure.

BEA-055055
No transaction

Category:
JMSClientExceptions

Cause:
A call to commit was made on a session but there is no current transaction.

Action:
Avoid calling commit on a session that is not currently in a transaction.

BEA-055056
Error committing session

Category:
JMSClientExceptions

Cause:
An error occurred while committing an XA session.

Action:
Examine the transaction logs to see what occurred to the transaction

BEA-055057
No transaction

Category:
JMSClientExceptions

Cause:
A call to rollback was made on a session but there is no current transaction.

Action:
Do not call rollback on a session that is not currently in a transaction.

BEA-055058
Error committing session

Category:
JMSClientExceptions

Cause:
An error occurred while committing an XA session.

Action:
Examine the transaction logs to see what occurred to the transaction.

BEA-055059
getXAResource can be called only from the server.

Category:
JMSClientExceptions

Cause:
A call to getXAResource was made from a client JVM; getXAResource is not supported in the client.

Action:
Avoid calling getXAResource from a client JVM.

BEA-055060
No transaction.

Category:
JMSClientExceptions

Cause:
A call to commit was made on a session but there is no current transaction.

Action:
Avoid calling commit on a session that is not currently in a transaction.

BEA-055061
No transaction.

Category:
JMSClientExceptions

Cause:
A call to rollback was made on a session but there is no current transaction.

Action:
Avoid calling rollback on a session that is not currently in a transaction.

BEA-055062
This session is transacted.

Category:
JMSClientExceptions

Cause:
A call to recover was made on a transacted session.

Action:
Avoid calling recover on a transacted session. Use rollback instead.

BEA-055063
This session has consumer listeners.

Category:
JMSClientExceptions

Cause:
The session on which setMessageListener was called already has consumer listeners.

Action:
Avoid calling setMessageListener on a session that already has consumer listeners.

BEA-055064
Unsupported topic operation on a queue session

Category:
JMSClientExceptions

Cause:
A call to createTopic was made on a QueueSession.

Action:
Avoid calling createTopic on a QueueSession.

BEA-055065
Unsupported topic operation {0} on a queue session.

Category:
JMSClientExceptions

Cause:
A call to {0} was made on a QueueSession.

Action:
Avoid calling {0} on a QueueSession.

BEA-055066
Unsupported topic operation on a queue session

Category:
JMSClientExceptions

Cause:
A call to createTemporaryTopic was made on a QueueSession.

Action:
Avoid calling createTemporaryTopic on a QueueSession.

BEA-055067
Unsupported topic operation on a queue session

Category:
JMSClientExceptions

Cause:
A call to unsubscribe was made on a QueueSession.

Action:
Avoid calling unsubscribe on a QueueSession.

BEA-055068
There is no subscription from which to unsubscribe.

Category:
JMSClientExceptions

Cause:
The user called unsubscribe on a session that does not have a subscription.

Action:
Avoid calling unsubscribe on a session that does not have a subscription.

BEA-055069
Unsupported queue operation on a topic session

Category:
JMSClientExceptions

Cause:
A call to createQueue was made on a TopicSession.

Action:
Avoid calling createQueue on a TopicSession.

BEA-055070
Unsupported queue operation on a topic session

Category:
JMSClientExceptions

Cause:
A call to createBrowser was made on a TopicSession.

Action:
Avoid calling createBrowser on a TopicSession.

BEA-055071
Unsupported queue operation on a topic session

Category:
JMSClientExceptions

Cause:
A call to createTemporaryQueue was made on a TopicSession.

Action:
Avoid calling createTemporaryQueue on a TopicSession.

BEA-055072
Wrong connection for this temporary destination

Category:
JMSClientExceptions

Cause:
An attempt was made to call createConsumer on an invalid connection from a temporary destination.

Action:
Create consumers using the same connection that was used to create the temporary destination.

BEA-055073
Dropping new message

Category:
JMSClientExceptions

Cause:
A new message is being dropped because too many messages have arrived.

Action:
Either consume messages faster or produce messages slower for this session.

BEA-055074
Dropping old message

Category:
JMSClientExceptions

Cause:
An old message is being dropped because too many messages have arrived.

Action:
Either consume messages faster or produce messages slower for this session.

BEA-055075
It is possible that the client is malfunctioning: a RuntimeException was thrown from its onMessage method.

Category:
JMSClientExceptions

Cause:
The onMessage method of the client threw a RuntimeException.

Action:
Modify the code such that the RuntimeException does not occur from within the body of the user code. This warning is required by section 4.5.2 of the JMS Specification.

BEA-055076
The session is closed.

Category:
JMSClientExceptions

Cause:
An operation was attempted on a closed session.

Action:
Avoid attempting this operation on a closed session.

BEA-055077
Cannot override producer destination.

Category:
JMSClientExceptions

Cause:
A call to send with a non-null destination was made on a producer that is already bound to a destination.

Action:
Avoid calling send with a non-null destination on a producer that is already bound to a destination.

BEA-055078
Cannot override producer destination

Category:
JMSClientExceptions

Cause:
A call to send with a non-null destination was made on a producer that is already bound to a destination.

Action:
Avoid calling send with a non-null destination on a producer that is already bound to a destination.

BEA-055079
Must provide destination to send to

Category:
JMSClientExceptions

Cause:
There is no destination to send to.

Action:
Use the version of send that has a destination or bind a destination to the producer before calling send.

BEA-055080
Must provide destination to send to

Category:
JMSClientExceptions

Cause:
There is no destination to send to.

Action:
Use the version of send that has a destination or bind a destination to the producer before calling send.

BEA-055081
Unsupported topic operation on a queue session

Category:
JMSClientExceptions

Cause:
A call to createDurableConnectionConsumer was made on a QueueConnection.

Action:
Avoid calling createDurableConnectionConsumer on a QueueConnection.

BEA-055082
The connection is closed.

Category:
JMSClientExceptions

Cause:
The connection has been closed. Only a few operations are valid on a closed connection.

Action:
Avoid calling any illegal operations on a closed queue connection.

BEA-055083
Cannot set clientid to {0}. The client ID is already set to {1}

Category:
JMSClientExceptions

Cause:
The clientID {1} is already set on this connection. The clientID cannot be set to {0}

Action:
Avoid attempting to set a clientID on a connection that already has one.

BEA-055084
A connection consumer works only on the server.

Category:
JMSClientExceptions

Cause:
A connection consumer can be created only in the same JVM in which the server is running.

Action:
Avoid attempting to create a connection consumer on a JVM that is not running the server.

BEA-055085
Destination is null.

Category:
JMSClientExceptions

Cause:
In a call to createConnectionConsumer or createConsumer, the destination parameter was null.

Action:
Avoid using null for the destination in a call to createConnectionConsumer or createConsumer.

BEA-055086
Foreign destination

Category:
JMSClientExceptions

Cause:
Foreign destinations are not supported when creating connectionConsumers.

Action:
Avoid using a foreign destination in a call to createConnectionConsumer.

BEA-055087
The session already has a message listener.

Category:
JMSClientExceptions

Cause:
A consumer may not have an individual message listener if its parent session already has one defined.

Action:
Avoid attempting to set a message listener for a consumer if the session already has a listener defined.

BEA-055088
The consumer is closed.

Category:
JMSClientExceptions

Cause:
The consumer has been closed. Only a few operations are valid on a closed consumer.

Action:
Avoid calling any illegal operations on a closed consumer.

BEA-055089
Destination is null.

Category:
JMSClientExceptions

Cause:
In a call to send, the destination parameter was null.

Action:
Avoid using null for the destination in a call to send.

BEA-055090
Foreign destination

Category:
JMSClientExceptions

Cause:
Foreign destinations are not supported when sending.

Action:
Avoid using a foreign destination in a call to send.

BEA-055091
Destination {0} must be a queue.

Category:
JMSClientExceptions

Cause:
An attempt was made to publish to a queue.

Action:
Avoid using publish to a queue. Use send instead.

BEA-055092
Destination {0} must be a topic.

Category:
JMSClientExceptions

Cause:
An attempt was made to send to a topic.

Action:
Avoid using send to a topic. Use publish instead.

BEA-055093
Error converting foreign message

Category:
JMSClientExceptions

Cause:
An I/O exception occurred while converting a foreign message. The cause of the failure may be contained in the linked exception.

Action:
Examine the linked I/O exception.

BEA-055094
The producer is closed.

Category:
JMSClientExceptions

Cause:
The producer has been closed. Only a few operations are valid on a closed producer.

Action:
Avoid calling any illegal operations on a closed producer.

BEA-055095
The browser is closed.

Category:
JMSClientExceptions

Cause:
The browser has been closed. Only a few operations are valid on a closed browser.

Action:
Avoid calling any illegal operations on a closed browser.

BEA-055096
Cannot convert null to a char.

Category:
JMSClientExceptions

Cause:
The null object cannot be converted to a char value.

Action:
Avoid passing null where a char value is expected.

BEA-055097
Cannot convert {0} to a char.

Category:
JMSClientExceptions

Cause:
An object that was not null, not a character, and not a string could not be converted to a char value.

Action:
Ensure that the object passed in is either a character or a string.

BEA-055098
Cannot convert null to an int.

Category:
JMSClientExceptions

Cause:
The null object cannot be converted to an int value.

Action:
Avoid passing null where an int value is expected.

BEA-055099
Cannot convert {0} to an int.

Category:
JMSClientExceptions

Cause:
An object that was not null, not an integer, and not a string could not be converted to an int value.

Action:
Ensure that the object passed in is either an integer or a string.

BEA-055100
Cannot convert null to a long.

Category:
JMSClientExceptions

Cause:
The null object cannot be converted to a long value.

Action:
Avoid passing null where a long value is expected.

BEA-055101
Cannot convert {0} to a long.

Category:
JMSClientExceptions

Cause:
An object that was not null, not a long, and not a string could not be converted to a long value.

Action:
Ensure that the object passed in is either a long or a string.

BEA-055102
Cannot convert null to a float.

Category:
JMSClientExceptions

Cause:
The null object cannot be converted to a float value.

Action:
Avoid passing null where a float value is expected.

BEA-055103
Cannot convert {0} to a float.

Category:
JMSClientExceptions

Cause:
An object that was not null, not a float, and not a string could not be converted to a float value.

Action:
Ensure that the object passed in is either a float or a string.

BEA-055104
Cannot convert null to a double.

Category:
JMSClientExceptions

Cause:
The null object cannot be converted to a double value.

Action:
Avoid passing null where a double value is expected.

BEA-055105
Cannot convert {0} to a double.

Category:
JMSClientExceptions

Cause:
An object that was not null, not a double, and not a string could not be converted to a short value.

Action:
Ensure that the object passed in is either a double or a string.

BEA-055106
A byte[] cannot be converted to a string.

Category:
JMSClientExceptions

Cause:
A byte[] cannot be converted to a string.

Action:
Avoid passing a byte array that needs to be converted to a string.

BEA-055107
Cannot convert {0} to a byte[].

Category:
JMSClientExceptions

Cause:
The given object could not be converted to a byte[].

Action:
Ensure that the object passed in can be converted to a byte array.

BEA-055108
Read past end of message.

Category:
JMSClientExceptions

Cause:
An attempt was made to read past the end of a StreamMessage. A linked EOFException may contain more information.

Action:
Avoid attempting to read past the end of a StreamMessage. See the linked EOFException for more information.

BEA-055109
Error reading from stream.

Category:
JMSClientExceptions

Cause:
There was an error reading the stream from a StreamMessage. A linked IOException may contain more information.

Action:
See the linked IOException for more information.

BEA-055110
Error writing to stream.

Category:
JMSClientExceptions

Cause:
There was an error writing to the stream of a StreamMessage. A linked IOException may contain more information.

Action:
See the linked IOException for more information.

BEA-055111
Cannot convert from {0} to {1}

Category:
JMSClientExceptions

Cause:
A StreamMessage was unable to convert one type to another.

Action:
Ensure that the two types are compatible. Avoid attempting to convert incompatible types.

BEA-055112
Error reading from stream.

Category:
JMSClientExceptions

Cause:
There was an error reading the stream from a StreamMessage. A linked ArrayIndexOutOfBoundsException may contain more information.

Action:
See the linked ArrayIndexOutOfBoundsException for more information.

BEA-055113
Error reading from stream.

Category:
JMSClientExceptions

Cause:
There was an error reading the stream from a StreamMessage. A linked ArrayStoreException may contain more information.

Action:
See the linked ArrayStoreException for more information.

BEA-055114
There was an eeror when deserializing an object. Some typical reasons for failure are: missing application class, application class version mismatch, or Java objects not being supported.

Category:
JMSClientExceptions

Cause:
There was an error deserializing an object. A linked IOException may have more details.

Action:
See the linked IOException for more details.

BEA-055115
Error deserializing an object.

Category:
JMSClientExceptions

Cause:
There was an error deserializing an object. A linked ClassNotFoundException may have more details.

Action:
See the linked ClassNotFoundException for more details.

BEA-055116
Internal error unknown message type {0}

Category:
JMSClientExceptions

Cause:
This error should never happen.

Action:
Contact My Oracle Support.

BEA-055117
Invalid delivery mode {0}

Category:
JMSClientExceptions

Cause:
The delivery mode passed into setJMSDeliveryMode is invalid

Action:
Change the code so that it calls setJMSDeliveryMode with a valid delivery mode.

BEA-055118
Invalid redelivery limit, must be >= -1.

Category:
JMSClientExceptions

Cause:
The redelivery limit parameter passed to setJMSRedeliveryLimit was invalid.

Action:
Change the code to pass a redelivery limit parameter that is >= -1.

BEA-055119
Invalid priority, {0}

Category:
JMSClientExceptions

Cause:
The priority parameter passed to setJMSPriority was invalid.

Action:
Change the code to pass a valid priority value.

BEA-055121
Invalid property name, "{0}"

Category:
JMSClientExceptions

Cause:
The property name passed to setObjectProperty was invalid.

Action:
Change the code to pass a valid property name.

BEA-055122
Property write attempted in READ mode.

Category:
JMSClientExceptions

Cause:
An attempt was made to write a property but the message is read-only.

Action:
Avoid attempting to write a property to a message in read-only mode.

BEA-055123
Invalid property value, {0}

Category:
JMSClientExceptions

Cause:
The property value passed to setObjectProperty was invalid.

Action:
Change the code to pass a valid property value.

BEA-055125
Unknown underlying stream type, cannot convert 6.0 class.

Category:
JMSClientExceptions

Cause:
While attempting to read a message created by an older version of WebLogic Server, a failure occurred.

Action:
It may not be possible to read the older version of the message. Contact My Oracle Support.

BEA-055126
Stream is corrupted. Possible older version

Category:
JMSClientExceptions

Cause:
While attempting to read a message created by an older version of WebLogic Server, a failure occurred.

Action:
It may not be possible to read the older version of the message. Contact My Oracle Support.

BEA-055127
Unsupported version

Category:
JMSClientExceptions

Cause:
The version of the message being read is unsupported.

Action:
Contact My Oracle Support.

BEA-055128
Read attempted in WRITE mode.

Category:
JMSClientExceptions

Cause:
An attempt was made to read a message in WRITE mode.

Action:
Avoid attempting to read a message in WRITE mode.

BEA-055129
Write attempted in READ mode.

Category:
JMSClientExceptions

Cause:
An attempt was made to write a message that is read-only.

Action:
Avoid attempting to write to a message in read-only mode.

BEA-055130
Invalid data type: {0}

Category:
JMSClientExceptions

Cause:
The class name given is not a valid data type. The type for setObject must be number, string, boolean, byte, character, or null.

Action:
Pass one of the acceptable data types to setObject in a MapMessage.

BEA-055131
Illegal name: {0}

Category:
JMSClientExceptions

Cause:
The given name is not legal. It is either null or of zero length.

Action:
Pass a non-null or non-zero-length string as the name of a MapMessage element.

BEA-055132
Could not copy message.

Category:
JMSClientExceptions

Cause:
The system could not copy a MapMessage. The linked IOException should contain more information about the nature of the error.

Action:
Examine the linked exception to discover what caused the failure.

BEA-055133
Could not deserialize message.

Category:
JMSClientExceptions

Cause:
The system could not deserialize a MapMessage. The linked IOException should contain more information about the nature of the error.

Action:
Examine the linked exception to discover what caused the failure.

BEA-055134
Unsupported class version {0}. Expected a value between {1} and {2} inclusive.

Category:
JMSClientExceptions

Cause:
While attempting to interoperate between different releases or service packs, an error occurred while attempting to serialize or deserialize an object. The version number of the object was not in the expected range. If {0} is larger than {1} then it is possible an attempt was made to access a newer JMS version than the current version. Otherwise a possible attempt has been made to interoperate with an unsupported older version of JMS.

Action:
Ensure that the versions of Oracle products that are interoperating are supported. If the versions should be supported, contact My Oracle Support.

BEA-055135
Could not write object, expected simple type, but got class {0}

Category:
JMSClientExceptions

Cause:
The given object class could not be written because it is not a simple type.

Action:
Contact My Oracle Support.

BEA-055136
Could not read object, unrecognized class code {0}.

Category:
JMSClientExceptions

Cause:
An unknown class code was received. The object cannot be read.

Action:
Contact My Oracle Support.

BEA-055137
JMSProducerSendResponse versions {0}, {1} not compatible with peer: {2}

Category:
JMSClientExceptions

Cause:
An interoperability error occurred.

Action:
Only use versions of Oracle products that can interoperate with each other. If the versions being used should interoperate, contact My Oracle Support.

BEA-055138
Peer not compatible with DistributedDestinationImpl version {0}. Peer Major Version is less than 6.

Category:
JMSClientExceptions

Cause:
An interoperability error occurred.

Action:
Only use versions of Oracle products that can interoperate with each other. If the versions being used should interoperate, contact My Oracle Support.

BEA-055139
Invalid Temporary Destination

Category:
JMSClientExceptions

Cause:
An attempt was made to delete an invalid temporary destination.

Action:
Avoid attempting to delete invalid temporary destinations.

BEA-055140
Internal error or marshalling error, unknown destination type {0}

Category:
JMSClientExceptions

Cause:
An unknown type was encountered when marshalling a destination.

Action:
Contact My Oracle Support.

BEA-055141
Destination is null.

Category:
JMSClientExceptions

Cause:
While checking a destination type, the incoming destination was null.

Action:
Avoid attempting to discover the type of a null destination.

BEA-055142
Foreign destination, {0}

Category:
JMSClientExceptions

Cause:
While checking a destination type, the incoming destination was foreign.

Action:
Avoid attempting to discover the type of a foreign destination.

BEA-055143
Destination must be a queue, {0}

Category:
JMSClientExceptions

Cause:
The given destination must be a queue, but it is not a queue.

Action:
Use the proper type of destination when checking types.

BEA-055144
Destination must be a topic, {0}

Category:
JMSClientExceptions

Cause:
The given destination must be a topic, but it is not a topic.

Action:
Use the proper type of destination when checking types.

BEA-055145
Unknown stream version: {0}

Category:
JMSClientExceptions

Cause:
The given version number is invalid for a buffered stream.

Action:
Contact My Oracle Support.

BEA-055146
The stream cannot handle raw objects.

Category:
JMSClientExceptions

Cause:
The stream is probably from an unintended source, such as a Web browser.

Action:
Only connect to the Oracle product TCP port with a proper client. If the client is a proper client, contact My Oracle Support.

BEA-055147
Not implemented

Category:
JMSClientExceptions

Cause:
readLine was called, but it has not been implemented.

Action:
Contact My Oracle Support.

BEA-055148
The stream cannot handle raw objects.

Category:
JMSClientExceptions

Cause:
A raw object could not be written to the buffered stream.

Action:
Contact My Oracle Support.

BEA-055149
Attempt to read past end of message ({0})

Category:
JMSClientExceptions

Cause:
The end of the BytesMessage was reached, but an attempt was made to read past it. {0} indicates where the attempt was made and will only be significant to My Oracle Support.

Action:
Avoid attempting to read past the end of the BytesMessage.

BEA-055150
Error reading from stream ({0}).

Category:
JMSClientExceptions

Cause:
The linked IOException will have more detail on the cause of the failure.

Action:
Examine the linked exception to discover what caused the problem.

BEA-055151
Length ({0}) is negative.

Category:
JMSClientExceptions

Cause:
In a call to readBytes, the length parameter is negative.

Action:
Fix the code to ensure a negative length is not passed to readBytes.

BEA-055152
length ({0}) is greater than the length of the array ({1}).

Category:
JMSClientExceptions

Cause:
In a call to readBytes, the length parameter is larger than the size of the bytes array to fill.

Action:
Fix the code to ensure the length passed to readBytes is less than or equal to the length of the output array.

BEA-055153
Error writing to stream ({0}).

Category:
JMSClientExceptions

Cause:
The linked IOException will have more detail on the cause of the failure.

Action:
Examine the linked exception to discover what caused the problem.

BEA-055154
Invalid object type: {0}

Category:
JMSClientExceptions

Cause:
The object passed to writeObject is not valid.

Action:
Only send valid object types to writeObject. Example valid types include boolean, byte, short, and integer.

BEA-055155
Cannot forward message

Category:
JMSClientExceptions

Cause:
Modified received messages are not supported when using forward methods.

Action:
Avoid modifying a received message in a call to forward.

BEA-055156
Peer neither compatible with {0} or {1} or {2} or {3}. PeerInfo is {4}.

Category:
JMSClientExceptions

Cause:
A version mismatch occurred in a message.

Action:
Check for other log messages that give more information about the failure.

BEA-055157
Invalid compression threshold

Category:
JMSClientExceptions

Cause:
The compression threshold was invalid.

Action:
Change the code to pass a valid compression threshold.

BEA-055158
WebLogic Server JMS failed to decompress the message body.

Category:
JMSClientExceptions

Cause:
The linked IOException will have more detail on the cause of the failure.

Action:
Examine the linked exception to discover what caused the problem.

BEA-055159
Message consumer received a compressed message with unknown compression tag - {0}

Category:
JMSClientExceptions

Cause:
Contact My Oracle Support.

Action:
Contact My Oracle Support.

BEA-055160
WebLogic Server JMS failed to deserialize the text message.

Category:
JMSClientExceptions

Cause:
Contact My Oracle Support.

Action:
Contact My Oracle Support.

BEA-055161
Cannot forward foreign messages.

Category:
JMSClientExceptions

Cause:
Foreign messages are not supported when using forward methods.

Action:
Avoid forwarding a foreign message.

BEA-055162
WebLogic Server JMS failed to serialize the text message for interoperability.

Category:
JMSClientExceptions

Cause:
Contact My Oracle Support.

Action:
Contact My Oracle Support.

BEA-055163
WebLogic Server JMS failed to serialize the XML message for interoperability.

Category:
JMSClientExceptions

Cause:
Contact My Oracle Support.

Action:
Contact My Oracle Support.

BEA-055164
Cannot forward a message to a WebLogic Server instance prior than version 9.0.

Category:
JMSClientExceptions

Cause:
Cannot forward a message to a WebLogic Server instance prior than 9.0.

Action:
Avoid forwarding a message to a WebLogic Server instance prior than 9.0.

BEA-055165
The following exception has occurred: {0}.

Category:
JMSClientExceptions

Cause:
An error condition has occurred.

Action:
Look for the associated exception in the log or the program to see what the results are. In general, this stack trace will help in debugging an existing problem.

BEA-055167
Single session cannot support more than one synchronous message-prefetching consumer.

Category:
JMSClientExceptions

Cause:
There is another opened synchronous message-prefetching consumer.

Action:
Close the other synchronous message-prefetching consumer.

BEA-055168
Synchronous message-prefetching consumer cannot support user transaction.

Category:
JMSClientExceptions

Cause:
Synchronous message-prefetching consumer cannot support user transaction.

Action:
Disable the user transaction or the synchronous message-prefetching consumer in the jms connection factory setting.

BEA-055169
Network connection to server was lost.

Category:
JMSClientExceptions

Cause:
The network connection to the server was lost.

Action:
This is usually a recoverable error when the JMS client is using the auto-reconnect/failover feature. This error is exposed to the user (JMS client code developer) when the auto-reconnect feature cannot make a decision without user input on a particular course of action after failover. The user can consciously code to continue to use relevant refreshed JMS objects with a potential lowered quality of service such as duplicate/lost/out-of-order messages, or decide to close the relevant JMS object.

BEA-055170
Cannot convert string property from its internal format.

Category:
JMSClientExceptions

Cause:
The string property cannot be converted from its internal format.

Action:
Contact My Oracle Support.

BEA-055171
Failed to unsubscribe subscription "{0}", client ID "{1}". This connection has a client ID policy of UNRESTRICTED and cannot unsubscribe a durable subscription using the standard javax.jms.Session.unsubscribe() API.

Category:
JMSClientExceptions

Cause:
An attempt was made to unsubscribe a durable subscription using the standard javax.jms.Session.unsubscribe(String name) method from a connection that has a Client ID policy of UNRESTRICTED.

Action:
Use weblogic.jms.extensions.WLSession.unsubscribe(Topic topic, String name) API to unsubscribe a durable subscription from a connection that has a Client ID policy of UNRESTRICTED.

BEA-055172
Failed to unsubscribe subscription "{0}", client ID "{1}". This connection has a Client ID policy of UNRESTRICTED and cannot unsubscribe a durable subscription with a null topic or distributed topic instance.

Category:
JMSClientExceptions

Cause:
An attempt was made to unsubscribe a durable subscription with a null Topic object or a distributed topic object from a connection that has a Client ID policy of UNRESTRICTED.

Action:
Provide a standalone topic object or a member of a distributed topic when calling weblogic.jms.extensions.WLSession.unsubscribe(String topic, String name).

BEA-055173
Read past end of message ({0})

Category:
JMSClientExceptions

Cause:
An attempt was made to read past the end of a StreamMessage. A linked EOFException may contain more information

Action:
Do not attempt to read past the end of a StreamMessage. See the linked EOFException for more information

BEA-055174
Error reading from stream ({0})

Category:
JMSClientExceptions

Cause:
There was an error reading the stream from a StreamMessage. A linked IOException may contain more information

Action:
See the linked IOException for more information

BEA-055175
Error writing to stream ({0})

Category:
JMSClientExceptions

Cause:
There was an error writing to the stream of a StreamMessage. A linked IOException may contain more information

Action:
See the linked IOException for more information

BEA-055176
Active transaction detected during send, publish, or receive while using a non-XATransaction Resource Adapter.

Category:
JMSClientExceptions

Cause:
An active transaction was detected during send, publish, or receive while using a non-XATransaction Resource Adapter.

Action:
Use the XATransaction Resource Adapter instead.

BEA-055177
An invalid value ({0}) for session mode was specified.

Category:
JMSClientExceptions

Cause:
An invalid value of the sessionMode parameter was specified when creating a JMSContext. The only valid values are JMSContext.AUTO_ACKNOWLEDGE, JMSContext.CLIENT_ACKNOWLEDGE, JMSContext.DUPS_OK_ACKNOWLEDGE and JMSContext.SESSION_TRANSACTED

Action:
Change the code so that it passes in a valid session mode. See the JMS API for more information.

BEA-055178
This method may not be called in a Java EE web or EJB container

Category:
JMSClientExceptions

Cause:
The code calls a JMS method which the JMS, EJB or Java EE specification states must not be called in a Java EE web or EJB container. See section EE.6.7 "Java Message Service (JMS) 2.0 Requirements" in the Java EE 7 platform specification" and section 16.3.5 "JMS API Requirements" in the EJB 3.2 specification.

Action:
Change the code so that it uses methods that are valid a Java EE web or EJB container.

BEA-055179
JMSContext is closed

Category:
JMSClientExceptions

Cause:
The code called the close methods on a JMSContext which had been previously closed.

Action:
Change the code so that it uses a JMSContext that has not been closed.

BEA-055180
Cannot set the setClientID method on a JMSContext because the JMSContext is in an invalid state

Category:
JMSClientExceptions

Cause:
The setClientID method was called on a JMSContext when the JMSContext is in an invalid state. It only valid to call the setClientID method on a JMSContext immediately after the JMSContext has been created and before any other action on the JMSContext is taken. It is also only valid to call the setClientID method on a JMSContext if the client ID has not already been administratively configured.

Action:
Change the code to endure that the setClientID method on a JMSContext is only called immediately after the JMSContext has been created and before any other action on the JMSContext is taken, and only if the client ID has not already been administratively configured.

BEA-055181
Invalid client ID. Client ID may not be null.

Category:
JMSClientExceptions

Cause:
The setClientID method was called on a JMSContext but the specified client ID was null.

Action:
Change the code so that the specified client ID is neither null nor an empty string.

BEA-055182
Invalid client ID. Client ID may not be an empty string.

Category:
JMSClientExceptions

Cause:
The setClientID method was called on a JMSContext but the specified client ID was an empty string.

Action:
Change the code so that the specified client ID is neither null nor an empty string.

BEA-055183
JMSConsumer is closed

Category:
JMSClientExceptions

Cause:
The code called the close method on a JMSConsumer which had been previously closed.

Action:
Change the code so that it uses a JMSConsumer that has not been closed.

BEA-055184
Message is null

Category:
JMSClientExceptions

Cause:
The code called the send method on a JMSProducer with a null value for the message parameter.

Action:
Change the code so that the message parameter passed to the JMSProducer send method is not null

BEA-055185
An invalid value ({0}) for delivery mode was specified

Category:
JMSClientExceptions

Cause:
The setDeliveryMode method on JMSProducer was called with an invalid value of the deliveryMode parameter. The only valid values are DeliveryMode.NON_PERSISTENT, DeliveryMode.PERSISTENT.

Action:
Change the code so that it passes in a valid delivery mode. See the JMS API for more information.

BEA-055186
An invalid value ({0}) for message priority was specified

Category:
JMSClientExceptions

Cause:
The setPriority method on JMSProducer was called with an invalid value of the setPriority parameter. Priority must be a valie between 0 and 9.

Action:
Change the code so that it passes in a valid priority value. See the JMS API for more information.

BEA-055187
Message property name must not be null.

Category:
JMSClientExceptions

Cause:
The message property name parameter was null. This is not valid.

Action:
Change the code to pass a message property name which is not null.

BEA-055188
Message property name must not be an empty string

Category:
JMSClientExceptions

Cause:
The message property name parameter was an empty string. This is not valid.

Action:
Change the code to pass a message property name which is not an empty string.

BEA-055189
Message property value must not be of type ({0})

Category:
JMSClientExceptions

Cause:
The message property name was of an invalid type. A message property value must be of type Boolean, Byte, Short, Integer, Long, Float or Double.

Action:
Change the code to pass a message property value of a valid type. Valid types are Boolean, Byte, Short, Integer, Long, Float and Double.

BEA-055190
Message property name ({0}) must not be a reserved word

Category:
JMSClientExceptions

Cause:
The message property name is a reserved word. This is not valid. A message property name cannot be NOT, AND, OR, BETWEEN, LIKE, IN, IS, or ESCAPE.

Action:
Change the code to pass a message property name which is not a reserved word.

BEA-055191
Message property name ({0}) contains an invalid character.

Category:
JMSClientExceptions

Cause:
Message property name contains an invalid character. The first character must be a letter and subsequent characters must be either a letter or a digit. A letter is any character for which the method Character.isJavaLetter returns true. This includes '_' and '$'. A letter or digit is any character for which the method Character.isJavaLetterOrDigit returns true.

Action:
Change the code to pass a message property name which contains valid characters.

BEA-055192
Message property name ({0}) contains an invalid first character.

Category:
JMSClientExceptions

Cause:
Message property name contains an invalid start character. The first character must be a letter and subsequent characters must be either a letter or a digit. A letter is any character for which the method Character.isJavaLetter returns true. This includes '_' and '$'. A letter or digit is any character for which the method Character.isJavaLetterOrDigit returns true

Action:
Change the code to pass a message property name which contains valid characters.

BEA-055193
Message body is a {0} and cannot be assigned to the specified class {1}

Category:
JMSClientExceptions

Cause:
Message body is a {0} and cannot be assigned to the specified class {1}. The application called the getBody method on a Message object. This method returns the message body as an object of the specified type. The message body must be capable of being assigned to the specified type. This means that the specified class or interface must be either the same as, or a superclass or superinterface of, the class of the message body.

Action:
Specify a class which is suitable for the actual body type

BEA-055194
Message body is a StreamMessage and the getBody method cannot be used

Category:
JMSClientExceptions

Cause:
The application called the getBody method on a Message object. Message body is a StreamMessage and the getBody method cannot be used with this type of message.

Action:
Use the methods specific to StreamMessage to obtain the message body. Do not use the getBody method.

BEA-055195
Shared durable connection consumers are not supported.

Category:
JMSClientExceptions

Cause:
The system does not support shared durable connection consumers.

Action:
Do not attempt to create a shared durable connection consumer.

BEA-055196
Shared connection consumers are not supported.

Category:
JMSClientExceptions

Cause:
The system does not support shared connection consumers.

Action:
Do not attempt to create a shared connection consumer.

BEA-055197
Invalid deliveryDelay , must be >= 0.

Category:
JMSClientExceptions

Cause:
The deliveryDelay parameter passed to setDeliveryDelay was invalid.

Action:
Change the code to pass a deliveryDelay parameter that is >= 0 .

BEA-055198
The JMS specification does not permit a message listener to call {0} on its own {1}.

Category:
JMSClientExceptions

Cause:
A message listener attempted to call {0} on its own {1}. This is not permitted by the JMS specification.

Action:
To conform to the JMS specification, change the message listener code so that it does not call {0} on its own {1}. Alternatively enable the connection factory setting AllowCloseInOnMessage to specify that this non-JMS behavior is permitted.

BEA-055199
An injected JMSContext cannot be used when there is neither a transaction nor a valid request scope.

Category:
JMSClientExceptions

Cause:
The application attempted to use an injected JMSContext when there was neither a Java EE transaction nor a CDI request scope.

Action:
Change the code to ensure that methods on the injected JMSContext are only called when there is a Java EE transaction or a valid CDI request scope. Alternatively, use an application-managed JMSContext (one created explicitly from a Connectionfactory) instead of an injected JMSContext.

BEA-055200
Asynchronous message forward is not currently supported.

Category:
JMSClientExceptions

Cause:
The application called the JMSProducer method setAsync before calling the JMSProducer method forward on the same JMSProducer object.

Action:
Remove the call to the JMSProducer method setAsync and try again. This will perform a synchronmous forward instead.

BEA-055201
An invalid value ({0}) for message priority was specified

Category:
JMSClientExceptions

Cause:
The send method on MessageProducer was called with an invalid priority value. Priority must be a value between 0 and 9.

Action:
Pass a valid priority value. See the JMS API for more information.

BEA-055202
An invalid value ({0}) for delivery mode was specified.

Category:
JMSClientExceptions

Cause:
The send method on MessageProducer was called with invalid delivery mode value. The only valid values are DeliveryMode.NON_PERSISTENT, DeliveryMode.PERSISTENT.

Action:
Pass a valid delivery mode value. See the JMS API for more information.

BEA-055203
The same Message object ({0}) was previously sent asynchronously but is not complete yet.

Category:
JMSClientExceptions

Cause:
A send method is called for a Message object that was asynchronously sent but is not complete yet.

Action:
Create a new Message object to send or wait for the asynchronous send to complete.

BEA-055204
JMS asynchronous send is not supported in an XA transaction.

Category:
JMSClientExceptions

Cause:
A JMS asynchronous send was used in an XA transaction.

Action:
Do not attempt to use asynchronous send in an XA transaction.

BEA-055205
There is no message body.

Category:
JMSClientExceptions

Cause:
There is no message body in the message.

Action:
Do not attempt to get the message body from a message that has no message body.

BEA-055206
CompletionListener is null.

Category:
JMSClientExceptions

Cause:
A null CompletionListener was passed to the asynchronous send method.

Action:
Do not pass a null CompletionListener to the JMS asynchronous send method.

BEA-055207
The Security Policy setting for JMS Connection Factory ({0}) is ({1}) which is not compatible with a Thread Based InitialContext.

Category:
JMSClientExceptions

Cause:
The Security Policy setting for JMS Connection Factory ({0}) is ({1}) which is not compatible with a Thread Based InitialContext.

Action:
Use an Object Based InitialContext to lookup the connection factory instead of a Thread Based InitialContext, or set a different Security Policy.

BEA-055208
Object based InitialContext does not support to lookup type "{0}".

Category:
JMSClientExceptions

Cause:
Object based InitialContext only support to lookup three types: jndi context, WLJMS CF and WLJMS destinaton.

Action:
Use a WL standard InitialContext to lookup other types.

BEA-055209
Foreign Server is not supported by Object Based InitialContext.

Category:
JMSClientExceptions

Cause:
Foreign Server is not supported by Object Based InitialContext. Looking up the local JNDI name of the Foreign Server is not supported by Object Based InitialContext.

Action:
Do not use Object Based InitialContext to look up the local JNDI name of the Foreign Server.

BEA-055210
Object based InitialContext does not support the "{0}" method.

Category:
JMSClientExceptions

Cause:
Object based InitialContext does not support the "{0}" method.

Action:
Do not call this method with Object Based InitialContext or use a WL standard InitialContext instead.

BEA-055211
Object based InitialContext only support the "{0}" method on server side and install client.

Category:
JMSClientExceptions

Cause:
Object based InitialContext only support the "{0}" method on server side and install client, does not support it on other client.

Action:
Call this method on server side or install client, do not call it on other client.

BEA-080001
Error in dispatcher {0}

Category:
RMI

Cause:
A runtime error occurred while dispatching a request to the server.

Action:
If the error is not application related, contact My Oracle Support with the stack trace for further analysis.

BEA-080002
Unexport failed for: {0}.

Category:
RMI

Cause:
The remote object was unexported twice.

Action:
No action is required.

BEA-080003
A RuntimeException was generated by the RMI server: {0} {1}.

Category:
RMI

Cause:
A runtime exception occurred while dispatching the request to the server.

Action:
No action is required.

BEA-080004
An error was generated by the RMI server: {0} {1}.

Category:
RMI

Cause:
A runtime error occurred while dispatching a response to the client.

Action:
The associated stack trace contains information about the error. Check the server logs for more details.

BEA-080005
An exception was generated by the RMI server: {0} {1}.

Category:
RMI

Cause:
The error response could not be sent to the client. The underlying socket caused an IOException while dispatching the error response.

Action:
The associated stack trace contains information about the error.

BEA-080006
Failed to associate the transaction context with the response while marshalling an exception to the client: {0}.

Category:
RMI

Cause:
An IOException occurred while associating a transaction context with the response. This happened when marshalling an exception in the response. Most likely, the socket has been torn down or an error occurred in the stream.

Action:
Check the server logs for more details.

BEA-080007
RMI runtime is disabled, since it could not initialize the DGC {0}.

Category:
RMI

Cause:
RMI runtime could not be initialized.

Action:
Restart the server. If the problem continues, contact My Oracle Support with the stack trace information.

BEA-080008
Failed to send error reply to client {0}.

Category:
RMI

Cause:
An exception occurred while dispatching an error response to the client.

Action:
No action is required.

BEA-080009
An error was generated by the RMI server: {0} invoking: {1}.

Category:
RMI

Cause:
A java.lang.Error occurred while invoking method {1} on {0}. A ServerError occurred due to the server side RMI method call.

Action:
Check the nested exception in the ServerError for more details.

BEA-080011
Empty workingSet found while assembling the heartbeat for {0}.

Category:
RMI

Cause:
An empty set of references for {0} was found while assembling the deterministic garbage collector (DGC) heartbeats for all remote virtual machines that are referenced from this virtual machine.

Action:
If a java.rmi.NoSuchObjectException occurs, contact My Oracle Support.

BEA-080012
No workingSet found for {0} residing in {1}.

Category:
RMI

Cause:
An empty working set for {0} was found while periodically scanning the list of finalized references and decrementing the count for any reference found. This is related to the deterministic garbage collector (DGC).

Action:
If a java.rmi.NoSuchObjectException occurs, contact My Oracle Support for further analysis of the error.

BEA-080013
Reference for {0} not found in working set.

Category:
RMI

Cause:
Did not find {0} in the working set while attempting to decrement the reference count. This is related to the deterministic garbage collector (DGC).

Action:
If a java.rmi.NoSuchObjectException occurs, contact My Oracle Support for further analysis of the error.

BEA-080015
Could not mark references {0}.

Category:
RMI

Cause:
An exception occurred during the execution of the DGC trigger.

Action:
If a java.rmi.NoSuchObjectException occurs, contact My Oracle Support for further analysis of the error.

BEA-080016
No connection available to: {0}. References to objects hosted by it are in jeopardy.

Category:
RMI

Cause:
The client lost connection to the server {0}. If the server does not receive lease renewal messages on the server, RMI runtime removes the remote objects whose leases are not renewed.

Action:
If the server {0} has been shut down or crashed, no action is required. Otherwise, ensure that the network is healthy.

BEA-080017
Failed to renew lease for: {0} objects hosted by: {1}.

Category:
RMI

Cause:
This message is logged only in debug mode.

Action:
No action is required.

BEA-080019
Marked in: {0} milliseconds

Category:
RMI

Cause:
This message is logged only if the LogDGCStatistics debug flag is enabled.

Action:
No action is required.

BEA-080020
An exception occurred in the DGC server sweep {0}.

Category:
RMI

Cause:
A runtime error occurred while the DGC server (host of remote objects) requested a sweep to periodically clean up server references.

Action:
Provide the log files to My Oracle Support for further analysis of the problem.

BEA-080021
Sweep freed: {0} objects in: {1} milliseconds. {2} exported objects remain.

Category:
RMI

Cause:
This message is logged only if the LogDGCStatistics debug flag is enabled.

Action:
No action is required.

BEA-080022
Tried to enroll lost reference: {0}.

Category:
RMI

Cause:
This message is logged when an attempt is made to increment the reference count of a lost reference. The reference may have already been released.

Action:
If a java.rmi.NoSuchObjectException occurs, contact My Oracle Support for further analysis of the error.

BEA-080023
Tried to unenroll a lost reference: {0}.

Category:
RMI

Cause:
This message is logged only if the DebugDGCEnrollment flag is enabled for debugging.

Action:
No action is required.

BEA-080024
Tried to renew the lease on the lost reference: {0}.

Category:
RMI

Cause:
This message is logged only if the DebugDGCEnrollment flag is enabled for debugging.

Action:
No action is required.

BEA-080026
Exporting remote object {0} with ID {1}.

Category:
RMI

Cause:
When a remote object is exported into RMI, RMI runtime assigns an object ID to it, thus setting up the environment for remote invocation.

Action:
This is an informational message. No action is required.

BEA-080027
A heartbeat was not sent due to probable client disconnect.

Category:
RMI

Cause:
A thin-client was disconnected from the server.

Action:
This is an informational message. No action is required.

BEA-080028
Failover attempt failed: {0} after {1} retries

Category:
RMI

Cause:
The cause was {0}

Action:
Please check the trace message.

BEA-090058
A Security Provider Exception occurred in a non-default AuditProvider {0}

Category:
Security

Cause:
A Security exception occurred during an audit write event.

Action:
Check errors or access permissions for the Auditing provider.

BEA-090059
The "{0}" AccessDecision class encountered an invalid Principal while attempting to check access to a WebLogic resource. Error: {1}

Category:
Security

Cause:
It is possible for this error to occur if a user has been deleted from a security realm while that user is still active.

Action:
If the user was mistakenly removed from the security realm, define them in the security realm again. Otherwise, no action is needed.

BEA-090060
The AccessDecision class "{0}" returned an error: {1}.

Category:
Security

Cause:
There are multiple possible causes.

Action:
Carefully read the returned error to determine if any action is required.

BEA-090063
The DeployableRoleMapper "{0}" returned an error: {1}.

Category:
Security

Cause:
There are multiple possible causes.

Action:
Carefully read the returned error to determine if any action is required.

BEA-090064
The DeployableAuthorizer "{0}" returned an error: {1}.

Category:
Security

Cause:
There are multiple possible causes.

Action:
Carefully read the returned error to determine if any action is required.

BEA-090074
Initializing {0} provider using LDIF template file {1}.

Category:
Security

Cause:
Either this is the first time this security provider has been initialized or the marker file indicating initialization (with a .initialized extension) has been removed from the system.

Action:
Look for a matching LoadedLDIFFFForProvider message which indicates the successful loading the LDIF information for this security provider.

BEA-090075
The {0} provider has had its LDIF information loaded from: {1}

Category:
Security

Cause:
The provider was requested to import data.

Action:
No action is required.

BEA-090076
A failure occurred attempting to load LDIF for provider {0} from file {1}.

Category:
Security

Cause:
An exception occurred attempting to open a temporary file as part of the load process.

Action:
Examine the exception and correct the cause.

BEA-090118
LDIF template file {1} was empty. The WebLogic provider {0} has been bootstrapped but has not been initialized with any LDIF data.

Category:
Security

Cause:
A WebLogic provider LDIF template file may have been overwritten with an empty file.

Action:
If the server boots successfully, no action is needed. If the server does not boot successfully then an attempt should be made to recover non-empty LDIFT template file from the WebLogic Server kit.

BEA-090119
LDIF template file {1} not found. The WebLogic provider {0} has been bootstrapped but has not been initialized with any LDIF data.

Category:
Security

Cause:
A WebLogic provider LDIF template file may have been deleted by mistake.

Action:
If the server boots successfully, no action is needed. If the server does not boot successfully, an attempt should be made to recover the LDIFT template file from the WebLogic Server kit.

BEA-090126
Unable to read a valid version number for property {0} from file {1}. Received exception {2}.

Category:
Security

Cause:
The value for the {0} property may have been corrupted.

Action:
Shutdown the server. Attempt to determine what the proper value for the {0} property should be and edit the file so that it reflects that value. If it is not possible to determine the proper value for the {0} property, edit the file and reset the {0} value to 0. Reboot WebLogic Server.

BEA-090127
Encountered a {2} exception while attempting to read from file {1} for WebLogic {0} provider.

Category:
Security

Cause:
The {1} file may have been deleted while it was being accessed.

Action:
Shutdown the server. Attempt to restore the file from a backup. If no backup is available,reboot the server. Note that the default WebLogic provider might not be correctly initialized.

BEA-090129
Updating {0} provider to version {2} using LDIF update template file {1}.

Category:
Security

Cause:
This security provider has not yet been updated or the marker file indicating initialization (with a .initialized extension) has been removed.

Action:
Look for a matching LoadedLDIFFForProvider message in the log file which indicates success loading the LDIF information for this security provider.

BEA-090130
Failure {3} while attempting to update the LDIF to version {2} in file {1} for WebLogic {0} provider.

Category:
Security

Cause:
The directory into which the {1} is to be written may not be writable, the file may not be writable, or the file may not be a valid properties file.

Action:
Ensure both the directory and file are writable. If they are writable, restore the file from backup or open the file and see if the properties within it are corrupt and correct accordingly. The version for provider {0} needs to be set to {2} in the file.

BEA-090131
Could not create a {0} JDK keystore instance. Exception: {1}

Category:
Security

Cause:
{0} is not a valid JDK keystore type or the JDK keystore type is not properly configured.

Action:
Verify that the correct keystore type was specified and that the keystore type is correctly specified in the java.security file. Verify that the code for the JDK keystore is in the JDK extensions directory. Reboot the server. after correcting the problem.

BEA-090132
Could not open the keystore file {0} for read access. Exception: {1}

Category:
Security

Cause:
The file does not exist, the file is a directory rather than a regular file or the file cannot be opened for reading.

Action:
Verify that the correct path to the keystore file was specified and that the keystore file exists. Reboot the server after correcting the problem.

BEA-090133
Could not load a {1} keystore from the file {0}. Exception: {2}

Category:
Security

Cause:
There is an I/O or format problem with the keystore data.

Action:
Verify that the path to the keystore, the keystore type, and the password for the keystore were specified correctly. Note that some keystore types (for example, JKS) do not require a password for read-only access. Read the exception text for more help on diagnosing the problem. Reboot the server after correcting the problem.

BEA-090134
Could not load a {1} keystore from the file {0}. Exception: {2}

Category:
Security

Cause:
Some certificates in the keystore could not be loaded.

Action:
Verify that the crypto providers required by the certificates in the keystore are properly configured in the java.security file and that their code is in the JDK extensions directory. Look at the exception text for more information on diagnosing the problem. Reboot the server after correcting the problem.

BEA-090135
Could not load a {1} keystore from the file {0}. Exception: {2}

Category:
Security

Cause:
The algorithm used to check the integrity of the keystore cannot be found.

Action:
Verify that the algorithm used to check the keystore integrity is properly configured in the java.security file and that the code is in the JDK extensions directory. Read the exception text for more information on diagnosing the problem. Reboot the server after correcting the problem.

BEA-090161
A failure occurred attempting to save LDIF for security provider {0} using file {1}.

Category:
Security

Cause:
An exception occurred attempting to open a temporary file as part of the export process.

Action:
Examine the exception and correct the cause.

BEA-090162
The {0} provider has had its LDIF information saved in: {1}

Category:
Security

Cause:
The security provider was requested to export data.

Action:
No action is required.

BEA-090163
The {0} provider did not import a duplicate entry: {1}

Category:
Security

Cause:
The security provider already contained the imported data.

Action:
Delete the existing data and import data into the security provider again.

BEA-090234
The Auditing Provider is not initialized.

Category:
Security

Cause:
The WebLogic Auditing provider was not initialized before the writeEvent method was called.

Action:
Ensure that the WebLogic Auditing provider has been initialized before events are written.

BEA-090235
Invalid Audit Severity

Category:
Security

Cause:
The Audit severity value is invalid or not supported.

Action:
Verify the Audit severity value passed to the setAuditSeverity method.

BEA-090236
DefaultAuthenticatorImpl constructor failed: {0}

Category:
Security

Cause:
An exception was thrown in the constructor of the WebLogic Authentication provider.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090237
Validation of old password failed

Category:
Security

Cause:
The old password was not valid.

Action:
Pass in the correct old password to the changeUserPassword method.

BEA-090239
Identity Assertion type cannot be null

Category:
Security

Cause:
The token type was null.

Action:
The containers should not be passing a null token type. This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090240
Identity Assertion token cannot be null

Category:
Security

Cause:
The identity assertion token was null.

Action:
The containers should not be passing a null token. This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090241
Identity Assertion type of {0} is not a configured active type

Category:
Security

Cause:
The identity assertion token type was not configured in the WebLogic Identity Assertion provider.

Action:
Configure the identity assertion type {0} in the Active Types attribute of the WebLogic Identity Assertion provider.

BEA-090248
Unrecognized Callback

Category:
Security

Cause:
Callback type is not supported.

Action:
Verify that the LoginModule for the configured Authentication provider is only passing a NameCallback when calling the handle method.

BEA-090249
Cursor is null

Category:
Security

Cause:
A null cursor is not supported.

Action:
Modify the code to pass a non-null cursor.

BEA-090250
Cursor not found {0}

Category:
Security

Cause:
Cursor was not found in the list of valid cursors.

Action:
Verify that the cursor passed to the method is valid and was returned from a method that creates cursors. Examples of such methods are listUsers, listGroups and listRoles.

BEA-090251
haveCurrent error for cursor name {0}

Category:
Security

Cause:
LDAP exception during haveCurrent method.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090252
advance error for cursor name {0}

Category:
Security

Cause:
an LDAP exception occurred while advancing the list.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090253
close error for cursor name {0}

Category:
Security

Cause:
an LDAP exception occurred while closing this list cursor.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090254
name cannot be null

Category:
Security

Cause:
The name cannot be null in the setUserDescription, setGroupDescription, getUserDescription, or getGroupDescription methods.

Action:
Pass in a non-null name to the method.

BEA-090255
User or Group {0}

Category:
Security

Cause:
The user or group cannot be found.

Action:
Pass in a user or group that exists.

BEA-090256
Error setting description for {0}

Category:
Security

Cause:
an exception occurred while calling to modify the description in the server.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090257
group cannot be null

Category:
Security

Cause:
The group name cannot be null.

Action:
Pass in a non-null group name to the method.

BEA-090258
max cannot be < 0

Category:
Security

Cause:
The maximumToReturn value cannot be less than zero.

Action:
Pass in a maximumToReturn parameter value that is greater or equal to zero.

BEA-090259
Group {0} can not be found.

Category:
Security

Cause:
Group {0} does not exist in the server.

Action:
Pass in a group that exists.

BEA-090260
Error listing group members for {0}

Category:
Security

Cause:
an exception was thrown while searching for the group members in the store.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090261
wildcard cannot be null

Category:
Security

Cause:
Wildcard parameter is null.

Action:
Pass a non-null wildcard parameter to the method.

BEA-090262
Error listing groups {0}

Category:
Security

Cause:
an exception was thrown while searching for the groups in the store.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090263
parent group cannot be null

Category:
Security

Cause:
Parent group name is null.

Action:
Pass a non-null parent group name parameter to this method.

BEA-090264
member cannot be null

Category:
Security

Cause:
Member name is null.

Action:
Pass a non-null member name parameter to this method.

BEA-090265
member cannot be parent group

Category:
Security

Cause:
Member name and parent group name are the same value.

Action:
Change either the member name or parent group name parameters of this method.

BEA-090266
group name cannot be null

Category:
Security

Cause:
Group name cannot be null.

Action:
Pass a non-null group name to the method.

BEA-090267
Group {0}

Category:
Security

Cause:
Group {0} already exists in the LDAP server. Users and groups must have unique names.

Action:
Pass in a unique group name.

BEA-090268
Group {0}

Category:
Security

Cause:
User {0} already exists in the LDAP server. Users and groups must have unique names.

Action:
Pass in a unique user name.

BEA-090269
Error adding group {0}

Category:
Security

Cause:
an exception was thrown while adding the group in the store.

Action:
Users and groups must have unique names.

BEA-090270
group cannot be same as member

Category:
Security

Cause:
Member and group names must be unique.

Action:
Pass in a group and member name that are unique.

BEA-090271
Member {0} can not be found.

Category:
Security

Cause:
Member does not exist.

Action:
Pass in a member name that exists in the store.

BEA-090272
Error adding member {0} to {1}

Category:
Security

Cause:
an exception was thrown while adding the member to the group in the store.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090273
member cannot be group

Category:
Security

Cause:
Member and group names must be unique.

Action:
Pass in a group and member name that are unique.

BEA-090274
Error removing member {0} from {1}

Category:
Security

Cause:
an exception was thrown when removing the member from the group in the store.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090275
Error removing group {0}

Category:
Security

Cause:
an exception was thrown while removing the group from the store.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090276
Error removing group {0} invalid cursor

Category:
Security

Cause:
An InvalidCursorException exception was thrown while removing the group from the store.

Action:
This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090277
Error destroying provider:

Category:
Security

Cause:
an LDAP exception was thrown while removing all the users and groups from the LDAP server.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090278
Error listing member groups {0}

Category:
Security

Cause:
an LDAP exception was thrown while listing the member groups in the LDAP server.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090279
Error listing users {0}

Category:
Security

Cause:
an LDAP exception was thrown while listing the users in the LDAP server.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090280
user cannot be null

Category:
Security

Cause:
User name cannot be null.

Action:
Pass a non-null user name to the method.

BEA-090281
user name cannot be null

Category:
Security

Cause:
The user name cannot be null.

Action:
Pass a non-null user name to the method.

BEA-090282
password cannot be null

Category:
Security

Cause:
The password cannot be null.

Action:
Pass a non-null password to the method.

BEA-090283
User {0}

Category:
Security

Cause:
User {0} already exists in the LDAP server.

Action:
Pass in another user name.

BEA-090284
Group {0}

Category:
Security

Cause:
Group {0} already exists in the LDAP server. Groups and users must have unique names.

Action:
Pass in an user name that is not already an existing group.

BEA-090285
password must be at least {0} characters long

Category:
Security

Cause:
Password is not long enough.

Action:
Enter a password that meets the specified minimum length requirement.

BEA-090286
Error adding user {0}

Category:
Security

Cause:
an LDAP exception was thrown while adding the user to the LDAP server.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090287
User {0} can not be found.

Category:
Security

Cause:
User {0} does not exist in the server.

Action:
Pass a user name that exists.

BEA-090288
Invalid password for user {0}

Category:
Security

Cause:
The bind to the LDAP server using this user name and password failed.

Action:
Pass a valid password or use the resetPassword method which does not require the old password.

BEA-090289
Error changing password for {0}

Category:
Security

Cause:
an LDAP exception was thrown while modifying the password in the LDAP server.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090290
Error removing user {0}

Category:
Security

Cause:
an LDAP exception was thrown while removing the user from the server.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090291
{0} search scope ({1}) not recognized

Category:
Security

Cause:
Search scope {1} is not a valid value.

Action:
Change the User Search Scope attribute for the LDAP Authentication provider.

BEA-090293
Error creating provider

Category:
Security

Cause:
An LDAP exception was thrown when checking the LDAP hierarchy in the initialization of the provider.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090294
could not get connection

Category:
Security

Cause:
an LDAP exception was thrown because an LDAP connection could not be obtained from the connection pool.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090295
caught unexpected exception

Category:
Security

Cause:
An unexpected LDAP exception was thrown when calling LDAP methods.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090296
invalid URL {0}

Category:
Security

Cause:
an LDAP exception was thrown because of an invalid dynamic group URL.

Action:
Verify the dynamic group definition. Read the exception text for more information on diagnosing the problem.

BEA-090297
No CallbackHandler Specified

Category:
Security

Cause:
The callback handler is null.

Action:
This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090298
No Delegate Specified

Category:
Security

Cause:
The LDAP delegate is null.

Action:
This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090299
Username Not Supplied

Category:
Security

Cause:
The user name returned from the NameCallback cannot be null.

Action:
This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090300
Identity Assertion Failed: User {0} does not exist

Category:
Security

Cause:
User does not exist in the LDAP server.

Action:
Add the user to the LDAP server or configure the Identity Assertion provider to return a user that exists.

BEA-090301
Password Not Supplied

Category:
Security

Cause:
Password cannot be null.

Action:
This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090302
Authentication Failed: User {0} denied

Category:
Security

Cause:
The username and password could not bind to the LDAP server.

Action:
Verify the username and password.

BEA-090303
Authentication Failed: User {0} {1}

Category:
Security

Cause:
an LDAP exception caused the authentication of the user to fail.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090304
Authentication Failed: User {0} {1}

Category:
Security

Cause:
An unexpected exception caused the authentication of the user to fail.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090305
Authentication Failed Getting Groups for User {0} {1}

Category:
Security

Cause:
A group to which the user belongs was not found.

Action:
Verify the groups to which the user belongs.

BEA-090306
Authentication Failed Getting Groups for User {0} {1}

Category:
Security

Cause:
A Invalid Cursor, Invalid Parameter, or LDAP exception was thrown when looking up the groups of which the user is a member.

Action:
Read the exception text in {1} for more information on diagnosing the problem.

BEA-090307
DefaultAuthenticatorImpl constructor failed: {0}

Category:
Security

Cause:
A exception was thrown in the constructor for the WebLogic Authentication provider.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090308
Validation of old password failed

Category:
Security

Cause:
The old password was not valid.

Action:
Verify the old password. Optionally, use the resetPassword method to change the user password.

BEA-090310
Failed to create resource

Category:
Security

Cause:
An EnCreateException was thrown when creating the security policy.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090311
Failed to set resource expression

Category:
Security

Cause:
An EnCreateException was thrown when setting the security policy expression.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090313
policy removal error

Category:
Security

Cause:
A EnRemoveException was thrown during the deletion of security policies for the application.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090314
Entitlement Engine unable to connect to the embedded LDAP server {0}

Category:
Security

Cause:
An exception was thrown when initializing the entitlement engine for the WebLogic Authorization provider.

Action:
Read the exception text in {0} for more information on diagnosing the problem.

BEA-090315
DefaultAuthorizerImpl init failed: {0}

Category:
Security

Cause:
An exception was thrown during the initialization of the WebLogic Authorization provider.

Action:
Read the exception text in {0} for more information on diagnosing the problem.

BEA-090316
null helper

Category:
Security

Cause:
The helper cannot be null.

Action:
This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090317
bug in PredicateArgument

Category:
Security

Cause:
The arguments for the predicate are invalid.

Action:
Verify the definition of the condition expression of the security policy.

BEA-090318
DefaultRoleMapperImpl init failed: {0}

Category:
Security

Cause:
An exception was thrown in the initialization method of the WebLogic Role Mapping provider.

Action:
Read the exception text in {0} for more information on diagnosing the problem.

BEA-090319
Unknown resource type: {0}

Category:
Security

Cause:
The role id cannot be null.

Action:
This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090320
Failed to create role

Category:
Security

Cause:
An exception was thrown during the createRole method.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090321
Failed to set role expression

Category:
Security

Cause:
An exception was thrown during the setRole method.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090322
role removal error

Category:
Security

Cause:
An EnRemoveException was thrown during the delete operation.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090324
DefaultCredentialMapperImpl init failed: {0}

Category:
Security

Cause:
An exception was thrown during the initialization of the WebLogic Credential Mapping provider.

Action:
Read the exception text in {0} for more information on diagnosing the problem.

BEA-090326
DefaultCredentialMapperImpl.listCredentials got LDAP exception

Category:
Security

Cause:
An LDAP exception was thrown while accessing the LDAP server to get the list of credentials for this WebLogic resource.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090327
DefaultCredentialMapperImpl.getCurrentCredentialRemoteUsername failed: No such credentials list cursor available

Category:
Security

Cause:
Cursor is invalid.

Action:
Verify that the cursor was returned from the listCredentials method.

BEA-090329
DefaultCredentialMapperImpl.listMappings got LDAP exception

Category:
Security

Cause:
An LDAP exception was thrown while accessing the LDAP server to get the list of credential mappings for this WebLogic resource.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090330
DefaultCredentialMapperImpl.getCurrentMappingWLSUsername failed: No such resource maps list cursor available

Category:
Security

Cause:
Cursor is invalid.

Action:
Verify that the cursor was returned from the listMappings method.

BEA-090331
DefaultCredentialMapperImpl.getCurrentMappingRemoteUsername failed: No such resource maps list cursor available

Category:
Security

Cause:
Cursor is invalid.

Action:
Verify that the cursor was returned from the listMappings method.

BEA-090332
DefaultCredentialMapperImpl.getRemoteUserName got LDAP exception

Category:
Security

Cause:
An LDAP exception was thrown while accessing the LDAP server to get the credential map or the credential map principal.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090333
DefaultCredentialMapperImpl.getRemotePassword got LDAP exception

Category:
Security

Cause:
An LDAP exception was thrown while accessing the LDAP server to get the password for the credential map.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090334
DefaultCredentialMapperImpl.setUserPasswordCredential got LDAP exception

Category:
Security

Cause:
An LDAP exception was thrown while accessing the LDAP server to set the password for the credential map.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090335
DefaultCredentialMapperImpl.setUserPasswordCredentialMapping got LDAP exception

Category:
Security

Cause:
An LDAP exception was thrown while accessing the LDAP server to set the credential resource map.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090336
DefaultCredentialMapperImpl.removeUserPasswordCredential got LDAP exception

Category:
Security

Cause:
An LDAP exception was thrown while accessing the LDAP server to remove the user password credential.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090337
DefaultCredentialMapperImpl.removeUserPasswordCredentialMapping got LDAP exception

Category:
Security

Cause:
An LDAP exception was thrown while accessing the LDAP server to remove the user password credential mapping.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090339
Could not create file output stream {0}

Category:
Security

Cause:
An IO exception was thrown during the create of either the temporary file or the real file for the Audit log.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090367
This method not yet implemented

Category:
Security

Cause:
Method is not implemented and should not be used.

Action:
This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090375
Null TokenType Parameter

Category:
Security

Cause:
The token type is null.

Action:
The containers should not pass a null token types. This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090377
Identity Assertion Failed, {0}

Category:
Security

Cause:
An IdentityAssertion exception was thrown in the assertIdentity or assertChallengeIdentity method of the Identity Assertion provider

Action:
Read the exception text in {0} for more information on diagnosing the problem.

BEA-090380
Identity Assertion Failed, Unsupported Token Type: {0}

Category:
Security

Cause:
Token type is not configured as an active type.

Action:
Define the token type {0} in the Active Types attribute of the configured Identity Assertion provider.

BEA-090393
Security service not yet initialized: {0}

Category:
Security

Cause:
The Security service must be initialized before it can be used.

Action:
This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090442
location null or empty

Category:
Security

Cause:
A keystore filename must not be null or a zero length string.

Action:
Set the keystore location to a valid filename.

BEA-090443
null file

Category:
Security

Cause:
The load and store methods require a non-null filename.

Action:
Pass a valid filename to the keystore load or store method.

BEA-090447
invalid flag value {0}

Category:
Security

Cause:
The value specified for the LoginModule control flag is not supported.

Action:
Pass in a valid value for the LoginModule control flag. Valid values are REQUIRED, OPTIONAL, REQUISITE, or SUFFICIENT.

BEA-090448
Invalid Format: {0}

Category:
Security

Cause:
Import format is either null, zero length, or not supported by this provider.

Action:
Pass in a supported format.

BEA-090449
Invalid Constraints

Category:
Security

Cause:
Constraints are not supported.

Action:
Do not pass constraints to the provider.

BEA-090450
Invalid name supplied

Category:
Security

Cause:
The filename, domain name, or security realm name cannot be null.

Action:
Pass a non null filename, domain name, or security realm name.

BEA-090451
Unable to read file: {0}

Category:
Security

Cause:
Import file cannot be read.

Action:
Verify the import filename.

BEA-090453
Import File Error

Category:
Security

Cause:
An IO exception was thrown while importing from the file.

Action:
Verify the import filename. Read the exception text or the associated log message for more information on diagnosing the problem.

BEA-090455
Export File Error

Category:
Security

Cause:
An IO exception was thrown while exporting to the file.

Action:
Verify the export filename. Read the exception text or the associated log message for more information on diagnosing the problem.

BEA-090469
Invalid file format

Category:
Security

Cause:
LDIF template file did not contain any substitution entries and does not have the correct file format.

Action:
Verify that the file specified to the import operation is really a LDIF template file produced by an export operation.

BEA-090473
DefaultAuthorizerImpl search failed: {0}

Category:
Security

Cause:
An exception was thrown trying to access the data store.

Action:
Look at the exception text in {0} for more information on diagnosing the problem.

BEA-090474
Unable to create temporary file: {0}

Category:
Security

Cause:
The java.io.tmpdir system property is not set correctly or the temporary directory is not writeable.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090511
The following exception has occurred:

Category:
Security

Cause:
An error condition has occurred.

Action:
Read the associated exception in the log or in application to determine the problem. In general, a stack trace can be used to debug an existing problem.

BEA-090512
The WebLogic Auditing provider failed to register to listen for AuditorMBean attribute change notifications

Category:
Security

Cause:
The installation of WebLogic Server is corrupt.

Action:
In order for a change in the auditing severity to take effect, the server needs to be rebooted.

BEA-090516
The {0} provider has preexisting LDAP data.

Category:
Security

Cause:
The provider was initialized during a previous boot of the WebLogic Server

Action:
No action necessary.

BEA-090517
Group {0} cannot be added to group {1} since group {0} is already ancestor of group {1}.

Category:
Security

Cause:
Group membership can not be circular..

Action:
Ensure that group membership is not circular. Add this group to a different group.

BEA-090545
DefaultRoleMapperImpl search failed: {0}

Category:
Security

Cause:
An exception was thrown trying to access the data store.

Action:
Look at the exception text in {0} for more information on diagnosing the problem.

BEA-090553
Invalid system property value: {0}={1}

Category:
Security

Cause:
Invalid system property value was passed on the command line.

Action:
Make sure the property value is valid and restart the server.

BEA-090555
The DefaultCredentialMapper could not get credentials. The requestor is {0}. The initiator is {1}. The resource is {2}. The exception is {3}.

Category:
Security

Cause:
An unexpected exception occurred when trying to get credentials.

Action:
Read the exception text from the log message for more information on diagnosing the problem.

BEA-090583
The EndCertificateSelector constructor was passed an illegal X509Certificate.

Category:
Security

Cause:
The X509Certificate must not be null.

Action:
Pass a valid X509Certificate to the EndCertificateSelector constructor.

BEA-090584
The IssuerDNSerialNumberSelector constructor was passed an illegal issuer DN.

Category:
Security

Cause:
The issuer DN must not be null or empty.

Action:
Pass a valid issuer DN to the IssuerDNSerialNumberSelector constructor.

BEA-090585
The IssuerDNSerialNumberSelector constructor was passed an illegal serial number.

Category:
Security

Cause:
The serial number must not be null.

Action:
Pass a valid serial number to the IssuerDNSerialNumberSelector constructor.

BEA-090586
The SubjectDNSelector constructor was passed an illegal subject DN.

Category:
Security

Cause:
The subject DN must not be null or empty.

Action:
Pass a valid subject DN to the SubjectDNSelector constructor.

BEA-090587
The SubjectKeyIdentifierSelector constructor was passed an illegal subject key identifier.

Category:
Security

Cause:
The subject key identifier must not be null or empty.

Action:
Pass a valid subject key identifier to the SubjectKeyIdentifierSelector constructor.

BEA-090588
The WLSCertPathBuilderResult constructor was passed an illegal Certpath.

Category:
Security

Cause:
The CertPath must not be null or empty.

Action:
Pass a valid CertPath to the WLSCertPathBuilderResult constructor. It must at least contain the end certificate of the cert chain."

BEA-090593
The realm {0} has an illegal cert path builder configured. To correct the problem, select one of the realm"s cert path providers as the realm"s cert path builder.

Category:
Security

Cause:
The realm {0} has an illegal cert path builder configured.

Action:
To correct the problem, select one of the realm"s cert path providers as the realm"s cert path builder.

BEA-090594
The {0} cert path security provider was passed an illegal CertPathParameters.

Category:
Security

Cause:
The CertPathParameters must be a weblogic.security.spi.CertPathBuilderParametersSpi.

Action:
The {0} cert path security provider must not be called directly by application code.

BEA-090595
The {0} cert path security provider was passed an illegal CertPathParameters.

Category:
Security

Cause:
The CertPathParameters must be a weblogic.security.spi.CertPathValidatorParametersSpi.

Action:
The {0} cert path security provider must not be called directly by application code.

BEA-090596
The WebLogicCertPathProvider was passed an unsupported CertPathSelector.

Category:
Security

Cause:
The CertPathSelector must be an EndCertificateSelector.

Action:
Pass an EndCertificateSelector to the WebLogicCertPathProvider.

BEA-090597
The CertificateRegistry was passed an unsupported CertPathSelector.

Category:
Security

Cause:
The CertPathSelector must be an EndCertificateSelector, IssuerDNSerialNumberSelector, SubjectDNSelector or SubjectKeyIdentifierSelector.

Action:
Pass an EndCertificateSelector, IssuerDNSerialNumberSelector, SubjectDNSelector or SubjectKeyIdentifierSelector to the CertificateRegistry.

BEA-090603
The certificate chain is invalid because it could not be completed. The trusted CAs did not include {0}.

Category:
Security

Cause:
The trusted CAs did not include {0}.

Action:
Add {0} to the chain or to the list of the trusted CAs if you want this chain to be validated.

BEA-090604
The certificate chain is invalid because none of its certificates is a trusted CA.

Category:
Security

Cause:
None of its certificates is a trusted CA.

Action:
Add one of the certificates in the chain to the list of of trusted CAs if you want this chain to be validated.

BEA-090605
The certificate chain is invalid because it contains the certificate {0} is either expired or is not currently valid.

Category:
Security

Cause:
The invalid certificate is {0}.

Action:
If this certificate is a trusted CA, and the certificate authority has issued a replacement certificate with the same subject DN and private key, and you want the certificate chain to be validated, then replace the trusted CA with the updated one. Otherwise, you must obtain a new certificate chain if you want the chain to be validated.

BEA-090606
The certificate chain is invalid because a certificate"s issuer DN "{0}" does not match it"s CA"s subject DN "{1}".

Category:
Security

Cause:
The certificate"s issuer DN is "{0}". The CA"s subject DN is "{1}".

Action:
You must obtain a new certificate chain if you want the chain to be validated.

BEA-090607
The certificate chain is invalid because of an encoding error for certificate {0}.

Category:
Security

Cause:
The invalid certificate is {0}.

Action:
Ensure that the certificate chain only contains certificates using RSA keys and that the JDK is configured to support RSA keys.

BEA-090608
The certificate chain is invalid because a certificate"s signature could not be validated by it"s CA"s public key. The invalid certificate is {0}. The CA is {1}.

Category:
Security

Cause:
Most likely, the wrong CA is in the chain for the certificate. The invalid certificate is {0}. The CA is {1}.

Action:
You must obtain a new certificate chain if you want the chain to be validated.

BEA-090609
The certificate chain is invalid because there is no JDK provider for certificate {0}.

Category:
Security

Cause:
The invalid certificate is {0}.

Action:
Ensure that the certificate chain only contains certificates using RSA keys and that the JDK is configured to support RSA keys.

BEA-090610
The certificate chain is invalid because there is no default JDK provider for certificate {0}.

Category:
Security

Cause:
The invalid certificate is {0}.

Action:
Ensure that the certificate chain only contains certificates using RSA keys and that the JDK is configured to support RSA keys.

BEA-090611
The certificate chain is invalid because a certificate"s signature could not be validated. The invalid certificate is {0}.

Category:
Security

Cause:
Most likely, the certificate has been tampered with. The invalid certificate is {0}.

Action:
You must obtain a new certificate chain if you want the chain to be validated.

BEA-090612
The certificate chain is invalid because it contains a certificate with an unsupported critical extension. The invalid certificate is {0}. The unsupported critical extension"s oid is {1}.

Category:
Security

Cause:
The invalid certificate is {0}. The unsupported critical extension"s oid is {1}.

Action:
You must obtain a new certificate chain if you want the chain to be validated.

BEA-090613
The certificate chain is invalid because it is longer than one of it"s CA"s allows. The CA is {0}. The chain length to that CA is {1}. The maximum chain length to that CA is {2}.

Category:
Security

Cause:
The CA is {0}. The chain length to that CA is {1}. The maximum chain length to that CA is {2}.

Action:
You must obtain a new certificate chain if you want the chain to be validated.

BEA-090614
The certificate chain is invalid because it contains a CA without basic constraints. The CA is {0}.

Category:
Security

Cause:
The CA is {0}.

Action:
You must obtain a new certificate chain if you want the chain to be validated.

BEA-090615
A CertPathBuilderParameters or CertPathValidatorParameters object was constructed with a list of trusted CAs that includes a null trusted CA.

Category:
Security

Cause:
A CertPathBuilderParameters or CertPathValidatorParameters object was constructed with a list of trusted CAs that includes a null trusted CA.

Action:
Ensure that the list of trusted CAs passed in does not include a null trusted CA.

BEA-090616
The configured CertPathBuilder provider returned an empty cert path.

Category:
Security

Cause:
The configured CertPathBuilder provider has a bug. It should never return an empty cert path.

Action:
Fix the bug in the configured CertPathBuilder.

BEA-090618
The WLS CertPathValidator was passed a null or empty cert path.

Category:
Security

Cause:
The WLS CertPathValidator was passed a null or empty cert path.

Action:
Pass a cert path containing at least one certificate to the WLS CertPathValidator.

BEA-090620
There is no JDK CertPathBuilder for algorithm {0}.

Category:
Security

Cause:
There is no JDK CertPathBuilder for algorithm {0}.

Action:
This is an internal WebLogic Server error in either the JDK or a WLS CertPathProvider.

BEA-090621
There is no JDK CertPathValidator for algorithm {0}.

Category:
Security

Cause:
There is no JDK CertPathValidator for algorithm {0}.

Action:
This is an internal WebLogic Server error in either the JDK or a WLS CertPathProvider.

BEA-090623
Failed to get the default trusted CAs for this server.

Category:
Security

Cause:
This exception is thrown when an exception occurs when finding this server"s trusted CAs.

Action:
Look at the exception text for more information on diagnosing the problem.

BEA-090624
Failed to create an X509 CertPath from an array of X509Certificates.

Category:
Security

Cause:
Failed to create an X509 CertPath from an array of X509Certificates.

Action:
Look at the exception text for more information on diagnosing the problem.

BEA-090635
No Results

Category:
Security

Cause:
There are no policies that match the search criteria.

Action:
No action necessary.

BEA-090636
No Results

Category:
Security

Cause:
There are no roles that match the search criteria.

Action:
No action necessary.

BEA-090637
No role name supplied

Category:
Security

Cause:
The role name is null or contains no data.

Action:
Specify a valid role name.

BEA-090638
No resource data

Category:
Security

Cause:
The resource data parameter was not supplied or is empty.

Action:
Specify valid resource data.

BEA-090639
No resource type

Category:
Security

Cause:
The resource type information was not supplied.

Action:
Specify a valid resource type.

BEA-090640
No resource identifier

Category:
Security

Cause:
The resource identifier parameter was not supplied or is empty.

Action:
Specify a valid resource identifier.

BEA-090641
No resource keys found

Category:
Security

Cause:
An invalid resource identifier was supplied.

Action:
Specify a valid resource identifier.

BEA-090642
Invalid data type for {0} resource key value

Category:
Security

Cause:
The data type of a resource key value is not valid.

Action:
Specify a valid resource key data type value.

BEA-090643
Invalid resource type: "{0}"

Category:
Security

Cause:
An invalid or unknown resource type was supplied.

Action:
Specify a valid resource type.

BEA-090644
Expected resource type: {0}

Category:
Security

Cause:
An invalid or unknown resource type was supplied.

Action:
Verify a valid resource type was supplied and contact BEA support.

BEA-090645
Expected resource key: {0}

Category:
Security

Cause:
An invalid resource identifier was supplied.

Action:
Specify a valid resource identifier.

BEA-090646
Unknown resource key: {0}

Category:
Security

Cause:
The resource key supplied in the resource data is unknown.

Action:
Specify only resource keys valid for a specific resource type.

BEA-090647
Invalid application name

Category:
Security

Cause:
The application name parameter was empty or contains invalid values.

Action:
Specify a valid application name.

BEA-090648
Invalid component name

Category:
Security

Cause:
The component name parameter was empty or contains invalid values.

Action:
Specify a valid component name.

BEA-090649
Illegal application search name

Category:
Security

Cause:
The application name was not a legal search string.

Action:
Specify a valid application name search string.

BEA-090650
Illegal component search name

Category:
Security

Cause:
The component name was not a legal search string.

Action:
Specify a valid component name search string.

BEA-090651
No component type

Category:
Security

Cause:
The component type parameter is empty.

Action:
Specify a valid component type of EJB, WebApp, Connector or WebService.

BEA-090652
Invalid component type: "{0}"

Category:
Security

Cause:
The component type parameter specified is not valid.

Action:
Specify a valid component type of EJB, WebApp, Connector or WebService.

BEA-090653
Empty array value found

Category:
Security

Cause:
An empty string was supplied for an array element of the resource key.

Action:
Specify a valid string.

BEA-090654
Unexpected resource identifier data: "{0}"

Category:
Security

Cause:
An invalid resource identifier was supplied.

Action:
Specify a valid resource identifier.

BEA-090655
Unexpected resource key array value: "{0}"

Category:
Security

Cause:
An invalid resource identifier was supplied.

Action:
Specify a valid resource identifier.

BEA-090656
Empty {0} resource {1} string

Category:
Security

Cause:
An empty string was supplied for an element of the resource.

Action:
Specify a valid string.

BEA-090657
Empty {0} resource {1} array string

Category:
Security

Cause:
An empty string was supplied for an array element of the resource.

Action:
Specify a valid string.

BEA-090662
The DeployableAuthorizer "{0}" implements the deprecated {1} interface.

Category:
Security

Cause:
At security provider initialization a deprecated security interface was detected.

Action:
No immediate action necessary. However, the security provider should be updated.

BEA-090663
The DeployableRoleMapper "{0}" implements the deprecated {1} interface.

Category:
Security

Cause:
At security provider initialization a deprecated security interface was detected.

Action:
No immediate action necessary. However, the security provider should be updated.

BEA-090666
Deploy handle not supplied

Category:
Security

Cause:
The deployment handle is null.

Action:
This exception is an internal WebLogic Server error. Contact BEA support.

BEA-090667
Application information not supplied

Category:
Security

Cause:
The application information is null.

Action:
This exception is an internal WebLogic Server error. Contact BEA support.

BEA-090671
Unable to get password digest for user name {0}

Category:
Security

Cause:
The user does not exist in the WebLogic authentication provider Embedded LDAP server or there is no password information available to calculate a digest.

Action:
Verify that the user exists in the WebLogic authentication provider, the authentication provider has the PasswordDigestEnabled attribute set to true, and the user entry has set the password since the attribute was set to true.

BEA-090683
The CertificateRegistry could not build a certificate path for end certificate {0}. This indicates that either someone is trying to access the server with an untrusted certificate or that the administrator has forgotten to register the certificate in the CertificateRegistry.

Category:
Security

Cause:
The CertificateRegistry does not contain the certificate {0}.

Action:
If you want to trust the end certificate {0}, then register it in the CertificateRegistry.

BEA-090684
The CertificateRegistry could not build a certificate path for the subject DN {0}. This indicates that either someone is trying to access the server with an untrusted subject DN or that the administrator has forgotten to register a certificate with this subject DN in the CertificateRegistry.

Category:
Security

Cause:
The CertificateRegistry does not contain a certificate whose subject DN is {0}.

Action:
If you want to trust the subject DN {0}, then register a certificate with this subject DN in the CertificateRegistry.

BEA-090685
The CertificateRegistry could not build a certificate path for the issuer DN {0} and serial number {1}. This indicates that either someone is trying to access the server with an untrusted issuer DN and serial number or that the administrator has forgotten to register a certificate with this issuer DN and serial number in the CertificateRegistry.

Category:
Security

Cause:
The CertificateRegistry does not contain a certificate whose issuer DN is {0} and whose serial number is {1}.

Action:
If you want to trust the issuer DN {0} and serial number {1}, then register a certificate with this issuer DN and serial number in the CertificateRegistry.

BEA-090686
The CertificateRegistry could not build a certificate path for the subject key identifier {0}. This indicates that either someone is trying to access the server with an untrusted subject key identifier or that the administrator has forgotten to register a certificate with this subject key identifier in the CertificateRegistry.

Category:
Security

Cause:
The CertificateRegistry does not contain a certificate whose subject key identifier is {0}.

Action:
If you want to trust the subject key identifier {0}, then register a certificate with this subject key identifier in the CertificateRegistry.

BEA-090687
The CertificateRegistry could not validate a certificate path whose end certificate is {0}. This indicates that either someone is trying to access the server with an untrusted certificate or that the administrator has forgotten to register the certificate in the CertificateRegistry.

Category:
Security

Cause:
The CertificateRegistry does not contain the certificate {0}.

Action:
If you want to trust the end certificate {0}, then register it in the CertificateRegistry.

BEA-090688
The maximum number of concurrent lists has been exceeded. The maximum is {0}. These lists are allocated by listing functions listAliases for the CertificateRegistry. Wait for some of the existing lists to either expire or be closed. Lists automatically expire if they have not been used for {1} milliseconds.

Category:
Security

Cause:
Either the server is under very heavy load, or someone is launching a denial service attack against the server or some application code (e.g. a client) is not closing lists after it finishes using them.

Action:
Wait for some of the existing lists to either time out or be closed.

BEA-090689
The certificate alias is null or empty.

Category:
Security

Cause:
An empty or null certificate alias is not supported.

Action:
Modify the code to pass a non-null and non-empty certificate alias.

BEA-090690
The file name is null or empty.

Category:
Security

Cause:
An empty or null file name is not supported.

Action:
Modify the code to pass a non-null and non-empty file name.

BEA-090691
The certificate alias wildcard is null or empty.

Category:
Security

Cause:
An empty or null certificate alias wildcard is not supported.

Action:
Modify the code to pass a non-null and non-empty certificate alias wildcard.

BEA-090692
max cannot be < 0

Category:
Security

Cause:
The maximumToReturn value cannot be less than zero.

Action:
Pass in a maximumToReturn parameter value that is greater or equal to zero.

BEA-090693
Certificate alias {0} not found.

Category:
Security

Cause:
The alias cannot be found.

Action:
Pass in a certificate alias that exists.

BEA-090694
The security provider already has a certificate registered under the alias {0}.

Category:
Security

Cause:
Certificate alias {0} already exists in the security provider.

Action:
Pass in another certificate alias.

BEA-090695
Subject DN {0} already registered under the alias {1}

Category:
Security

Cause:
A certificate with subject DN {0} already exists in the security provider under the alias {1}.

Action:
Either remove the previous certificate from the security provider or register a different certificate.

BEA-090696
Issuer DN {0} and serial number {1} already registered under the alias {2}

Category:
Security

Cause:
A certificate with issuer DN {0} and serial number {1} already exists in the security provider under the alias {2}.

Action:
Either remove the previous certificate from the security provider or register a different certificate.

BEA-090697
Subject key identifier {0} already registered under the alias {1}

Category:
Security

Cause:
A certificate with subject key identifier {0} already exists in the security provider under the alias {1}.

Action:
Either remove the previous certificate from the security provider or register a different certificate.

BEA-090698
Errors occurred while importing data into this security provider.

Category:
Security

Cause:
Some of the data could not be imported into this security provider.

Action:
The getExceptions method on the ErrorCollectionException thrown by this method may be used to get a list of the errors that occurred.

BEA-090699
Errors occurred while exporting data from this security provider.

Category:
Security

Cause:
Some of the data could not be exported from this security provider.

Action:
The getExceptions method on the ErrorCollectionException thrown by this method may be used to get a list of the errors that occurred.

BEA-090710
Unable to write the file {0}.

Category:
Security

Cause:
Examine the nested exception for more information in diagnosing the problem.

Action:
Verify that the file is not a directory or a read-only file.

BEA-090711
Unable to read the file {0}.

Category:
Security

Cause:
Examine the nested exception for more information in diagnosing the problem.

Action:
Verify that the file exists and is not a directory.

BEA-090712
Unable to read the JKS keystore {0}.

Category:
Security

Cause:
Examine the nested exception for more information in diagnosing the problem.

Action:
Verify that the file is a JKS keystore.

BEA-090713
Unable to read the certificate in the PEM or DER file {0}.

Category:
Security

Cause:
Examine the nested exception for more information in diagnosing the problem.

Action:
Verify that the file is a PEM or DER file containing a single certificate.

BEA-090724
Challenge identity assertion has not completed, subject is not available yet

Category:
Security

Cause:
The method to get the subject was called before the identity assertion has completed.

Action:
Call the hasChallengeIdentityCompleted method before calling the method to get the subject.

BEA-090726
Unexpected exception while reading credential attribute: {0}

Category:
Security

Cause:
LDAP connection failure, corrupted LDAP database, or invalid cursor.

Action:
Verify that LDAP is up and running.

BEA-090728
Failed to read credential of type {0} stored under alias {1}

Category:
Security

Cause:
LDAP connection failure, or the database is corrupted.

Action:
Verify that LDAP is up and running.

BEA-090731
Unable to retrieve query

Category:
Security

Cause:
The internal query structure was not able to be retrieved from the connection. This could potentially be caused by a misconfigured DBMS ATN provider, but is more likely caused by an internal coding error in the DBMS ATN provider.

Action:
Review JDBC connection pool configuration, and provider level SQL Query settings. If these appear valid, this exception may indicate an internal coding error in the DBMS ATN provider. Contact BEA support.

BEA-090732
Invalid data source name specified: {0}

Category:
Security

Cause:
The DBMS ATN provider was most likely configured with an invalid data source name

Action:
Review and correct the data source name in the DBMS ATN provider configuration

BEA-090734
The connection pool was not usable

Category:
Security

Cause:
The DBMS ATN provider or the connection pool it is configured to use may be misconfigured or unavailable.

Action:
Review the JDBC related configuration in the server and the DBMS ATN provider configuration, and test the JDBC connection pool.

BEA-090735
The DBMS connection was not usable

Category:
Security

Cause:
The DBMS ATN provider or the connection pool it is configured to use may be misconfigured or unavailable.

Action:
Review the JDBC related configuration in the server and the DBMS ATN provider configuration, and test the JDBC connection pool.

BEA-090736
An exception occurred while validating the {0} configuration settings

Category:
Security

Cause:
An unexpected exception was thrown while validating configuration settings. This may indicate a configuration problem, or it may be an internal coding error

Action:
Review the exception trace for details on the cause, if the cause and solution are not apparent, contact BEA support.

BEA-090737
An exception occurred while getting connection to validate the configuration settings

Category:
Security

Cause:
An exception was thrown while validating configuration settings. This may indicate a configuration problem, or it may be an internal coding error

Action:
Review the exception trace for details on the cause, if the cause and solution are not apparent, contact BEA support.

BEA-090738
The {0} password hash algorithm is not usable

Category:
Security

Cause:
The password algorithm name was not found to be supported by the JCE crypto configuration

Action:
Verify the password algorithm is specified correctly, and that the JCE configuration supports the algorithm.

BEA-090739
The SQL statement for {0} does not appear to be correct

Category:
Security

Cause:
The DBMS SQL providers attempt to validate the configured SQL statements are correct. The validation code detected something was wrong with the configured SQL.

Action:
Review and correct the SQL statement.

BEA-090740
An unexpected exception occurred while calling the {0} method of the user defined DBMS sub plugin

Category:
Security

Cause:
The DBMS pluggable runtime providers caught an unexpected exception while calling the user defined sub plugin. The cause likely resides in the user defined sub plugin.

Action:
Review the exception details and the user defined sub plugin code to determine the cause and action.

BEA-090741
A SQLException occurred while calling the {0} method of the user defined DBMS sub plugin

Category:
Security

Cause:
The DBMS pluggable runtime providers caught a SQLException while calling the user defined sub plugin. The cause could be a database connectivity issue, or it could reside in the user defined sub plugin.

Action:
Review the exception details and the user defined sub plugin code to determine the cause and action.

BEA-090742
The DBMS pluggable runtime sub plugin failed to load

Category:
Security

Cause:
The DBMS pluggable runtime provider was not able to load the user defined sub plugin.

Action:
Review the DBMS pluggable runtime provider configuration. Verify the name of the user defined sub plugin class is correct, and that it is present in the server classpath.

BEA-090743
An unexpected exception occurred while loading the {0} sub plugin class

Category:
Security

Cause:
The DBMS pluggable runtime provider was not able to load the user defined sub plugin class and the exception thrown was not expected.

Action:
Review the exception details and the sub plugin configuration.

BEA-090744
The DBMS sub plugin class {0} was not found

Category:
Security

Cause:
The user defined sub plugin class was not found

Action:
Verify the name of the user defined sub plugin class is correct, and that it is present in the server classpath.

BEA-090745
The DBMS sub plugin class {0} was not the correct type

Category:
Security

Cause:
The user defined sub plugin class was not the correct type. Either the wrong class was specified, or the sub plugin was not coded correctly

Action:
Verify the user defined sub plugin class name is correct and that it implements the correct interface.

BEA-090746
The DBMS sub plugin class {0} was not able to be accessed

Category:
Security

Cause:
The user defined sub plugin class was not able to be accessed. Either the wrong class was specified, or the sub plugin was not coded correctly

Action:
Verify the user defined sub plugin class name is correct, that it implements the correct interface, and that the class is publicly accessible.

BEA-090747
The DBMS sub plugin class {0} was not able to be instantiated

Category:
Security

Cause:
The user defined sub plugin class was not able to be instantiated. Either the wrong class was specified, or the sub plugin was not coded correctly

Action:
Verify the user defined sub plugin class name is correct, that it implements the correct interface, it is defined as a class, and it is not an abstract class.

BEA-090748
There was a failure closing the DBMS connection

Category:
Security

Cause:
The exception information should be reviewed to determine the cause.

Action:
Review the exception details to determine if action is required.

BEA-090751
Failed to retrieve the prepared statement for {0}

Category:
Security

Cause:
Failed to retrieve the prepared statement for {0}, this is potentially an internal coding error

Action:
Review the JDBC configuration, contact BEA support if the cause is not apparent

BEA-090752
The password type in the DBMS was not a supported type

Category:
Security

Cause:
It is most likely caused by the password field in the DBMS stored as an unexpected type, binary or char data is expected.

Action:
Review the type for the password field in the database to ensure it is either binary or char data

BEA-090753
Hash algorithm {0} was not found

Category:
Security

Cause:
The JCE configuration is most likely not setup to support the algorithm

Action:
Review the JCE configuration to ensure the hash algorithm is available for use.

BEA-090754
The DBMS authenticator provider login module was not properly initialized

Category:
Security

Cause:
The DBMS authentication provider configuration may be incorrect, or there could be an internal coding error.

Action:
Review the DBMS authentication provider configuration. If no cause is found, contact BEA support.

BEA-090755
A database connection was not available from pool. Try increasing Connection Pool Size or Timeout

Category:
Security

Cause:
The connection pool size or timeout settings may need to be increased

Action:
Review the JDBC connection pool related configuration in the server, and consider increasing the connection pool size or timeout

BEA-090756
The DBMS provider was unable to form a query to access the {0} information

Category:
Security

Cause:
For SQL based DBMS providers configuration is most likely incorrect. For sub pluggable DBMS providers the user defined sub-plugin code could also be the cause.

Action:
Review and correct the DBMS provider configuration. If a sub pluggable provider is being used, also review the user defined sub plugin code.

BEA-090757
The DBMS provider got an exception when formatting the user

Category:
Security

Cause:
If a user defined sub-plugin for formatting the user was supplied, it may have a coding error

Action:
Review and correct the user defined sub-plugin user format code.

BEA-090758
The DBMS provider got an exception when formatting the groups

Category:
Security

Cause:
If a user defined sub-plugin for formatting the groups was supplied, it may have a coding error

Action:
Review and correct the user defined sub-plugin group format code.

BEA-090759
A SQLException occurred while retrieving {0} information

Category:
Security

Cause:
A SQLException occurred while retrieving {0} information

Action:
Review the exception details to determine the cause and action.

BEA-090760
The user {0} was not unique in the DBMS

Category:
Security

Cause:
This is caused by multiple records for the username existing in the DBMS

Action:
Review the DBMS records for the username.

BEA-090761
Authentication failed for user {0}

Category:
Security

Cause:
The exception details need to be reviewed to determine the cause

Action:
Review the exception details to determine the cause and action to take.

BEA-090762
Exception occurred in login module

Category:
Security

Cause:
The exception details need to be reviewed to determine the cause

Action:
Review the exception details to determine the cause and action to take.

BEA-090765
Failed to create policies for application version {0}

Category:
Security

Cause:
An exception was thrown during the application version created method.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090766
Failed to create roles for application version {0}

Category:
Security

Cause:
An exception was thrown during the application version created method.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090767
Failed to create credential mappings for application version {0}

Category:
Security

Cause:
An exception was thrown during the application version created method.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090768
credential mapping removal error

Category:
Security

Cause:
An unexpected exception occurred when trying to remove the credentials for a deleted application.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090769
The Active Directory ATN provider could not access the tokenGroups attribute for userDN {0} with principal {1} to perform group membership lookup.

Category:
Security

Cause:
The tokenGroups attribute was not accessible in the user entry. This is most likely the a problem with the Active Directory schema, or an Active Directory permission problem with the principal that is configured to access Active Directory.

Action:
Have the Active Directory administrator verify that the tokenGroup attribute is present in the Active Directory schema, and that the {1} principal has permission to read the tokenGroups attribute in Active Directory

BEA-090771
The Negotiate Identity Asserter was not configured with enough active types to perform negotiation.

Category:
Security

Cause:
The Negotiate Identity Asserter needs to be configured with all of its supported types specified as active types in order to perform negotiation.

Action:
Update the Negotiate Identity Asserter configuration to add all supported types listed for the provider to be active types.

BEA-090776
Exception when trying to generate a SAML assertion: {0}

Category:
Security

Cause:
An exception during the generation of a SAML assertion.

Action:
Read the exception text from the log message for more information on diagnosing the problem.

BEA-090777
Exception when trying to sign a SAML assertion: {0}

Category:
Security

Cause:
An exception during the signing of a SAML assertion.

Action:
Read the exception text from the log message for more information on diagnosing the problem.

BEA-090781
The SAMLLoginModule expected to receive a SAMLNameCallback and instead received a {0}.

Category:
Security

Cause:
This likely a configuration problem, if a SAMLIALoginModule is configured without a corresponding SAMLIdentityAsserter being configured.

Action:
Check the configuration of Identity Asserters and Login Modules.

BEA-090784
While Trying to find the groups that {0} belongs to,A Duplicate member {1} was detected.

Category:
Security

Cause:
A duplicate Membership in the groups was detected.

Action:
It might be possible that a cycle exists in the group entries.

BEA-090785
The Negotiate Identity Asserter found no identity to assert and no continuation was indicated.

Category:
Security

Cause:
This likely a configuration problem.

Action:
Check the configuration for the negotiate identity asserter and kerberos.

BEA-090786
The Negotiate Identity Asserter encountered an unexpected error processing a token.

Category:
Security

Cause:
This should not happen. This could be due to an invalid or corrupt SPNEGO token, or possibly some unknown token format similar to SPNEGO.

Action:
This exception indicates an internal coding error in the server. Contact BEA support.

BEA-090787
A Null DataSource name specified

Category:
Security

Cause:
A configuration setting that required a DataSource name was null.

Action:
Check configuration settings that require DataSource names to verify they are correctly specified.

BEA-090788
"Problem with DataSource/ConnectionPool configuration, verify DataSource name {0} is correct and Pool configurations are correct"

Category:
Security

Cause:
A configuration setting that required a DataSource name was likely incorrect, or the pool settings associated with it are incorrect.

Action:
Check configuration settings to ensure the DataSource name is correct and the associated pool configuration settings are correct

BEA-090789
The DBMS authentication provider encountered an unexpected exception during authentication.

Category:
Security

Cause:
An unexpected exception occurred during authentication.

Action:
Review the exception stack trace. If the cause is not obvious, contact BEA support

BEA-090790
BINARY or VARBINARY Result type is not allowed for this SQL statement {0}

Category:
Security

Cause:
The SQL statement result was a type that is not allowed for that statement

Action:
Review the SQL statement in the configuration to ensure it returns an appropriate type

BEA-090791
Result type is not {0} for SQL statement {1}

Category:
Security

Cause:
The SQL statement requires a result type of {0}

Action:
Review the SQL statement in the configuration to ensure it returns an appropriate type

BEA-090792
Parameter {0} type is not CHAR or VARCHAR for SQL statement {1}

Category:
Security

Cause:
The SQL statement parameter {0} requires a type of CHAR or VARCHAR

Action:
Review the SQL statement in the configuration to ensure the parameter types are correct

BEA-090793
Unexpected exception caught accepting the kerberos context, verify the JCE configuration is correct in java.security and the sun.security.jgss.SunProvider is configured

Category:
Security

Cause:
The exception stack should be reviewed, but this could be due to the JCE configuration in java.security not having the sun.security.jgss.SunProvider configured

Action:
Verify the JCE configuration is correct. If it is correct, review the exception to determine the cause.

BEA-090794
Password hash algorithm was not specified

Category:
Security

Cause:
The configuration is most likely set with an empty password hash algorithm

Action:
Review the configuration to ensure the hash algorithm is specified correctly.

BEA-090795
No columns in SQL results, need 1 column for SQL statement {0}

Category:
Security

Cause:
The SQL statement requires a result

Action:
Review the SQL statement in the configuration to ensure it returns an appropriate number and type of result

BEA-090796
Number of parameters was expected to be {0} but was {1} for SQL statement {2}

Category:
Security

Cause:
The SQL statement requires a specific number of parameters, and the statement specified had a different number of parameters

Action:
Review the SQL statement in the configuration to ensure it has the expected number of parameters specified

BEA-090798
Invalid characters found in input {0}

Category:
Security

Cause:
Input was specified that had invalid characters in it

Action:
Review the rejected input to determine what invalid characters were specified and enter the input without them

BEA-090799
PKICredentialMapperImpl init failed: {0}

Category:
Security

Cause:
An exception was thrown during the initialization of the WebLogic PKI Credential Mapping provider.

Action:
Read the exception text in {0} for more information on diagnosing the problem.

BEA-090800
Value for argument {0} for the credential type {1} not found.

Category:
Security

Cause:
Value for {0} for credential type {1} does not exist in the LDAP server.

Action:
Pass a value that exists.

BEA-090801
Value for resource {0}, initiator name {1} representing user name {2} with credential action {3} for the credential type {4} not found.

Category:
Security

Cause:
Value for resource {0}, initiator name {1} representing user name {2} with credential action {3} for the credential type {4} does not exist in the LDAP server.

Action:
Pass the values that exists.

BEA-090802
PKI Credential Mapper has got an LDAP exception.

Category:
Security

Cause:
An LDAP exception was thrown while accessing the LDAP server to set the Key Pair mapping.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090803
PKI Credential Mapper has got an LDAP exception.

Category:
Security

Cause:
An LDAP exception was thrown while accessing the LDAP server to set the Public Certificate Mapping.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090804
Credential of the type {0} could not be removed.

Category:
Security

Cause:
An LDAP exception was thrown while accessing the LDAP server.

Action:
Check if the LDAP serer is up and running.

BEA-090805
Failed to read credential for Resource {0}, initiator name {1} representing user name {2} with credential action {3} for the credential type {4}.

Category:
Security

Cause:
LDAP connection failure, or the database is corrupted.

Action:
Verify that LDAP is up and running.

BEA-090806
PKI Keystore at location {0} not found .

Category:
Security

Cause:
Keystore configured at location {0} for the PKI Credential Provider not found.

Action:
Please create the keystore that is configured for the PKI Credential Mapper.

BEA-090807
PKI Keystore at location {0} of the type {1} and of type {2} and could not be loaded with the password provided.

Category:
Security

Cause:
Either the keystore password provided was not correct or the keystore type and provider not correctly entered.

Action:
Configure the keystore properly.

BEA-090808
The keystore alias {0} provided does not exist in the keystore configured for the provider.

Category:
Security

Cause:
The alias provided does not exist in the keystore configured for the provider.

Action:
Configure the keystore with the alias provided.

BEA-090809
The key pair could not be retrieved from the keystore with the supplied alias {0} and its password.

Category:
Security

Cause:
Either the alias supplied does not represent a key pair or the password provided is incorrect.

Action:
Please configure the keystore with the key pair properly.

BEA-090810
The keystore alias {0} provided does not represent a certificate entry in the keystore.

Category:
Security

Cause:
The alias provided does not represent a certificate entry in the keystore.

Action:
Configure the keystore with the appropriate certificate entry.

BEA-090812
Could not create a {0} keystore instance for provider {1}. Exception: {2}

Category:
Security

Cause:
{0} is not a valid keystore type or keystore provider {1} was not properly configured.

Action:
Verify that the correct keystore type was specified and that the keystore provider is correctly specified in the java.security file.

BEA-090813
DefaultCredentialMapperImpl.getCurrentMappingResourceID failed: No such resource maps list cursor available

Category:
Security

Cause:
Cursor is invalid.

Action:
Verify that the cursor was returned from the listMappings method.

BEA-090815
The password provided for the keystore configured for the PKICredential Mapper was null.

Category:
Security

Cause:
The keystore password provided for the PKI Credential Mapper cannot be null.

Action:
Enter a valid password for the keystore configured for the PKI Credential Mapper.

BEA-090816
Error creating security configuration runtime: {0}

Category:
Security

Cause:
During initialization, the security runtime registers with the management infrastructure. If this process fails, a management exception is thrown.

Action:
Read the exception text for more information on diagnosing the problem.

BEA-090817
These configuration changes cannot be activated since the domain does not have a default realm configured.

Category:
Security

Cause:
The "DefaultRealm" is not set for the domain's SecurityConfiguration.

Action:
To correct the problem, set the "DefaultRealm" for the domain's SecurityConfiguration to one of its realms. If it does not have any realms, create and configure one.

BEA-090820
The internal variable {0} is null and it should not be.

Category:
Security

Cause:
Unknown.

Action:
This exception is an internal WebLogic Server error. Contact BEA support.

BEA-090821
The configured CertPathBuilder provider returned an unordered CertPath. {0} The CertPath is {1}

Category:
Security

Cause:
The configured CertPathBuilder provider has a bug. It should never return an unordered CertPath.

Action:
Fix the bug in the configured CertPathBuilder.

BEA-090824
Unable to generate SAML Assertion: {0}

Category:
Security

Cause:
The SAML assertion could not be generated due to incorrect SAML configuration or missing/incorrect parameters supplied to the assertion generator.

Action:
Check the SAML configuration.

BEA-090827
LDIF template file {1} was empty. The WebLogic provider {0} has been bootstrapped but has not been initialized with any LDIF data.

Category:
Security

Cause:
A WebLogic provider LDIF template file may have been overwritten with an empty file.

Action:
If the server boots successfully, no action is needed. If the server does not boot successfully then an attempt should be made to recover non-empty LDIFT template file from the WebLogic Server kit.

BEA-090828
Identity Assertion type cannot be null

Category:
Security

Cause:
The token type was null.

Action:
Null should not be passed as the token type.

BEA-090829
Identity Assertion token cannot be null

Category:
Security

Cause:
The identity assertion token was null.

Action:
Null should not be passed as the token.

BEA-090830
Identity Assertion type of {0} is not a valid token type for the LDAP X509 Identity Assertion provider.

Category:
Security

Cause:
The token type passed in did not match the LDAP X509 Identity Assertion token type.

Action:
Pass in the correct token type for the LDAP X509 Identity Assertion provider.

BEA-090831
Unrecognized Callback

Category:
Security

Cause:
Callback type is not supported.

Action:
Verify that the LoginModule for the configured Authentication provider is only passing a NameCallback when calling the handle method.

BEA-090832
No matching certificate found in the LDAP directory.

Category:
Security

Cause:
No matching certificate were found in the LDAP directory.

Action:
Verify that the appropriate certificates are present in the configured LDAP directory.

BEA-090833
No certificates found in the LDAP directory.

Category:
Security

Cause:
No certificates were found in the LDAP directory.

Action:
Verify that the appropriate certificates are present in the configured LDAP directory.

BEA-090834
No LDAP connection could be established.

Category:
Security

Cause:
The connection parameters provided were either not correct or the LDAP was offline.

Action:
Verify that the connection parameters provided are correct and the LDAP server is running.

BEA-090835
Required parameter not supplied when performing the management operation on the PKI Credential Provider.

Category:
Security

Cause:
A required parameter was null.

Action:
Please call the management operations with the appropriate parameters.

BEA-090836
The Keystore provider configured for PKICredential Mapper does not exist at location {0}.

Category:
Security

Cause:
The file {0} does not exist.

Action:
To use the PKICredentialProvider please point to an existing keystore. Reboot the server.

BEA-090837
The configured keystore location for the PKI Credential Mapper is either null or empty.

Category:
Security

Cause:
The PKI Credential provider location value was either set to null or empty.

Action:
Set the PKI Credential provider keystore location to a valid keystore location.

BEA-090841
SAMLServlet: Unexpected exception while handling {0} request.

Category:
Security

Cause:
SAML providers not configured correctly, internal server error, or malformed request.

Action:
Check SAML configuration and server status. If configuration is OK and server is operating normally, enable SAML debug logging for more information.

BEA-090842
SAMLServletAuthenticationFilter: Unexpected exception.

Category:
Security

Cause:
SAML providers not configured correctly, internal server error, or malformed request.

Action:
Check SAML configuration and server operation. If problem persists, enable SAML debug logging for more information.

BEA-090843
{0} provider initialization failed: {1} parameter is null.

Category:
Security

Cause:
Internal server error.

Action:
Try restarting server.

BEA-090844
{0} provider initialization failed: Invalid {1} property "{2}" for "{3}".

Category:
Security

Cause:
Incorrect provider configuration.

Action:
Check and update the indicated provider property.

BEA-090845
{0} provider initialization failed: Missing {1} property for "{2}".

Category:
Security

Cause:
Invalid provider configuration.

Action:
Check and update the indicated provider property.

BEA-090846
{0} provider initialization failed: Invalid {1} attribute "{2}".

Category:
Security

Cause:
Incorrect provider configuration.

Action:
Check and update the indicated provider attribute.

BEA-090847
{0} provider initialization failed: Missing {1} attribute.

Category:
Security

Cause:
Invalid provider configuration.

Action:
Check and update the indicated provider attribute.

BEA-090848
{0} provider initialization failed: Unexpected exception.

Category:
Security

Cause:
Internal server error.

Action:
Check server status.

BEA-090849
{0} provider initialization failed: Exception while initializing XML parsers.

Category:
Security

Cause:
Internal server error.

Action:
Check server.

BEA-090851
The {0} provider is initialized.

Category:
Security

Cause:
See the message body.

Action:
No action is required.

BEA-090853
SAMLIdentityAsserter initialization failed: Could not instantiate/initialize the used assertion cache class: {0}.

Category:
Security

Cause:
Invalid class name configured, class is not visible to the class loader, or initialization parameters are incorrect..

Action:
Check configuration of class name and initialization parameters. Check that class is installed in a valid location.

BEA-090854
{0} provider initialization failed: Could not retrieve credentials for {1}.

Category:
Security

Cause:
SSL identity not configured for server.

Action:
Check SSL configuration.

BEA-090856
{0} configuration update failed: Provider settings updated while not initialized.

Category:
Security

Cause:
Internal server error.

Action:
Check server.

BEA-090857
{0} provider initialization failed: Could not register MBean update listener.

Category:
Security

Cause:
Internal server error.

Action:
Check server.

BEA-090863
There was an error in the SAML CredentialMapper Cache subsystem. The exception is {0}.

Category:
Security

Cause:
The SAML Cache could have been misconfigured.

Action:
Please check the SAML Cache parameters and restart the server.

BEA-090869
The PolicyConsumer "{0}" returned an error: {1}.

Category:
Security

Cause:
There are multiple possible causes.

Action:
Carefully read the returned error to determine if any action is required.

BEA-090871
The RoleConsumer "{0}" returned an error: {1}.

Category:
Security

Cause:
There are multiple possible causes.

Action:
Carefully read the returned error to determine if any action is required.

BEA-090872
The {0} service can not be found for {1}

Category:
Security

Cause:
A null was returned when doing a service lookup

Action:
Check the configuration to see that the missing service was actually configured.

BEA-090873
Expected a {0} object but did not get one.

Category:
Security

Cause:
Possible configuration problem.

Action:
Check configuration.

BEA-090874
{0} returned a null {1}.

Category:
Security

Cause:
This should never happen.

Action:
Examine the specific objects referenced in the error message to see what may be the cause.

BEA-090875
Null parameter supplied to method {0}

Category:
Security

Cause:
A parameter was not correctly specified

Action:
This is most likely a coding error.

BEA-090876
{0}Consumer not configured

Category:
Security

Cause:
An attempt was made to reference a Consumer but none are configured

Action:
This is most likely a configuration error.

BEA-090878
Unknown token type: {0}

Category:
Security

Cause:
Likely caused by the token type not being properly configured.

Action:
This is most likely a configuration error.

BEA-090879
The certificate for the imported alias {0} is already in registry, certificate not imported

Category:
Security

Cause:
None

Action:
No action required.

BEA-090881
Management operation could not be performed

Category:
Security

Cause:
The administration server is not reachable.

Action:
Check that the administration server is running and available on the network.

BEA-090883
Resource name is null or empty.

Category:
Security

Cause:
Resource name should not be null or empty.

Action:
Check that the resource name is not null or empty.

BEA-090884
User name is null or empty.

Category:
Security

Cause:
User name should not be null or empty.

Action:
Check that the User name is not null or empty.

BEA-090885
Remote user name is null or empty.

Category:
Security

Cause:
Remote user name should not be null or empty.

Action:
Check that the Remote user name is not null or empty.

BEA-090886
List number should not be negative.

Category:
Security

Cause:
List number should not be negative.

Action:
Check that the list number is not negative.

BEA-090887
Can not find member {0} from group {1}.

Category:
Security

Cause:
Member {0} not exit in group {1}.

Action:
Check the group members.

BEA-090897
A failure occurred attempting to update XACML global policies for security provider {0}.

Category:
Security

Cause:
An exception occurred attempting to update XACML global policies.

Action:
Examine the exception and correct the cause.

BEA-090899
User attribute name cannot be null.

Category:
Security

Cause:
User attribute name is null for the request.

Action:
Please pass in user attribute name which is not null.

BEA-090900
User attribute name is not supported for specified operation.

Category:
Security

Cause:
User attribute name is not supported.

Action:
Please pass in user attribute name which is supported. Please refer to documentation for details.

BEA-090901
Invalid group name: {0}. Can not contain {1}.

Category:
Security

Cause:
Improper usage of {1}.

Action:
Never use a group name carrying {1}.

BEA-090902
The certificate chain received from {0} contained a V1 certificate which cannot be a CA.

Category:
Security

Cause:
The certificate chain received by the peer contained a V1 certificate which cannot be a CA. This is rejected by the basic constraints checking for strong and strict and not allowing V1 certificates as CAs, which protects against a specific certificate chain attack on SSL.

Action:
The peer certificate chain needs to be looked at carefully to determine which certificate is not correct. If the certificate chain really is from a valid peer, you should look at updating the peer certificate chain with valid CA certificates. If this is not possible, you can disable the basic constraints checking to allow the certificate chain to be accepted and allows this vulnerability to be exploited.

BEA-090905
Disabling CryptoJ JCE Provider self-integrity check for better startup performance. To enable this check, specify -D{0}=true

Category:
Security

Cause:
CryptoJ JCE Provider self-integrity check incurs some performance penalty at server startup.

Action:
No action needed.

BEA-090906
Changing the default Random Number Generator in RSA CryptoJ from {1} to {2}. To disable this change, specify -D{0}=true

Category:
Security

Cause:
CryptoJ's default RNG ECDRBG causes certain cryptographic operations slower.

Action:
No action needed.

BEA-090907
Invalid user name: {0}. Can not contain {1}.

Category:
Security

Cause:
Improper usage of {1}.

Action:
Never use a user name carrying {1}.

BEA-090908
Using the default WebLogic SSL Hostname Verifier implementation.

Category:
Security

Cause:
This is an informational message.

Action:
No action is required.

BEA-090909
Using the configured custom SSL Hostname Verifier implementation: {0}.

Category:
Security

Cause:
This is an informational message.

Action:
No action is required.

BEA-090910
Grant statement has invalid syntax: {0}

Category:
Security

Cause:
There is an error in the syntax of the grant statement.

Action:
Verify that the grant statement syntax is correct.

BEA-090911
Permission found in grant statement has invalid syntax: {0}

Category:
Security

Cause:
There is an error in the syntax of the permission within the grant statement.

Action:
Verify that the grant statement permission syntax is correct.

BEA-090912
Attempting to check revocation status for certificate with subject: {0}

Category:
Security

Cause:
X.509 certificate revocation checking is enabled.

Action:
No action is required.

BEA-090913
Unknown revocation status not causing failure for certificate with subject: {0}

Category:
Security

Cause:
X.509 certificate revocation checking is enabled, however, certificate revocation status cannot be determined, and is configured not to fail on an unknown status.

Action:
If validation failure is required, configure certificate revocation status to fail on an unknown status. To determine why the status is unknown, enable debug logging.

BEA-090914
Certificate revocation status: {0}

Category:
Security

Cause:
X.509 certificate revocation checking is enabled.

Action:
No action is required.

BEA-090915
Nonce was ignored by the OCSP responder, forcing certificate revocation status to be ignored and considered unknown: {0}.

Category:
Security

Cause:
X.509 certificate revocation checking is enabled, and OCSP is configured with nonces enabled.

Action:
To enable use of the ignored status, configure to disable OCSP nonces.

BEA-090916
Unknown revocation status causing failure for certificate with subject: {0}.

Category:
Security

Cause:
X.509 certificate revocation checking is enabled, certificate revocation status cannot be determined, and is configured to fail on an unknown status.

Action:
If validation failure is not required, configure certificate revocation status to not fail on an unknown status. To determine why the status is unknown, enable debug logging.

BEA-090917
Revoked certificate causing validation failure, certificate with subject: {0}.

Category:
Security

Cause:
X.509 certificate revocation checking is enabled, and the checked certificate was reported revoked.

Action:
Contact the certificate presenter (for example, SSL peer) and request that the revoked certificate be updated.

BEA-090918
Non-revoked certificate with subject: {0}.

Category:
Security

Cause:
X.509 certificate revocation checking is enabled, and the checked certificate was reported NOT revoked.

Action:
No action is required.

BEA-090919
The configured SSL minimum protocol version {0} is invalid or not supported. The minimum has been changed to {1}.

Category:
Security

Cause:
The current SSL implementation does not support the configured SSL minimum protocol version.

Action:
No action is required.

BEA-090920
Certicom SSL is available, however JSSE is being used for SSL, since JSSE has been selected by system property {0}, either explicitly or by default.

Category:
Security

Cause:
The system property {0} is selecting JSSE either explicitly or by default.

Action:
To use Certicom for SSL, set the system property {0} to false.

BEA-090921
JSSE has not been selected by system property {0}, however Certicom SSL is not available, so JSSE is being used for SSL.

Category:
Security

Cause:
Certicom SSL is not available, so JSSE is being used for SSL, even though JSSE was not selected.

Action:
To use Certicom for SSL, install Certicom.

BEA-090922
Certicom SSL is available, however JSSE is being used for SSL, since JSSE has been selected by the SSLMBean.JSSEEnabled attribute, either explicitly or by default.

Category:
Security

Cause:
The attribute SSLMBean.JSSEEnabled is selecting JSSE either explicitly or by default.

Action:
To use Certicom for SSL, set the attribute SSLMBean.JSSEEnabled to false.

BEA-090923
JSSE has not been selected by the SSLMBean.JSSEEnabled attribute, however Certicom SSL is not available, so JSSE is being used for SSL.

Category:
Security

Cause:
Certicom SSL is not available, so JSSE is being used for SSL, even though JSSE was not selected.

Action:
To use Certicom for SSL, install Certicom.

BEA-090924
JSSE has been selected by default, since the SSLMBean is not available.

Category:
Security

Cause:
This usually occurs early in server startup, before Management Service runtime access is available.

Action:
No action is required. Eventually the Management Service will start and normal operation will commence.

BEA-090925
JSSE has been selected by default, since the system property {0} has the invalid value "{1}".

Category:
Security

Cause:
The system property {0} was not set to "true" or "false".

Action:
Change the system property {0} value to be either "true" or "false".

BEA-090926
Illegal key store source value [keyStoreType="{0}", source="{1}", exception="{2}", message="{3}"]

Category:
Security

Cause:
The configured key store source value is not valid for the key store type.

Action:
Correct the key store source value, ensuring that the source is appropriate for the key store type. For example, the "jks" key store type requires that the source be a file path to an existing key store file.

BEA-090927
Illegal or unknown key store type value [keyStoreType="{0}", source="{1}"]

Category:
Security

Cause:
The configured key store type value is not recognized.

Action:
Correct the key store type value. For example, the "jks" key store type requires the type value to be "jks".

BEA-090928
Unable to instantiate key store [keyStoreType="{0}", provider="{1}", exception="{2}", message="{3}"]

Category:
Security

Cause:
Key store instantiation failure usually occurs because no appropriate specified or default provider is available. See the exception for details.

Action:
Verify that key store type is correct, and that a supporting Java Cryptography Architecture (JCA) provider is available in the Java Runtime Environment. A "jks" key store provider is usually available by default. An Oracle Key Store Service (type "kss") provider is only available if Oracle Java Required Files (JRF) is installed.

BEA-090929
Unable to load key store [keyStoreType="{0}", source="{1}", exception="{2}", message="{3}"]

Category:
Security

Cause:
A key store could fail to load due to an invalid source or password. Since key store instantiation succeeded, the key store type is valid. See the exception for details.

Action:
Check the configured key store source and password values.

BEA-090930
One of the Custom Identity Key Store attributes is not set on the channel override (NetworkAccessPointMBean). If any of the following attributes are set, then all of these attributes must be set: CustomIdentityKeyStoreFileName, CustomIdentityKeyStoreType, and either CustomIdentityKeyStorePassPhrase or CustomIdentityKeyStorePassPhraseEncrypted.

Category:
Security

Cause:
One of the following Custom Identity Key Store attributes are not set: CustomIdentityKeyStoreFileName, CustomIdentityKeyStoreType, and either CustomIdentityKeyStorePassPhrase or CustomIdentityKeyStorePassPhraseEncrypted.

Action:
Ensure all of the following attributes are set: CustomIdentityKeyStoreFileName, CustomIdentityKeyStoreType, and either CustomIdentityKeyStorePassPhrase or CustomIdentityKeyStorePassPhraseEncrypted.

BEA-090931
When overriding Custom Identity Key Store attributes, ChannelIdentityCustomized must be enabled.

Category:
Security

Cause:
ChannelIdentityCustomized is not enabled, and must be when the following Custom Identity Key Store attributes are set: CustomIdentityKeyStoreFileName, CustomIdentityKeyStoreType, and either CustomIdentityKeyStorePassPhrase or CustomIdentityKeyStorePassPhraseEncrypted.

Action:
Enable ChannelIdentityCustomized.

BEA-090932
When overriding Custom Identity Key Store attributes, CustomPrivateKeyAlias must be set on the channel override (NetworkAccessPointMBean).

Category:
Security

Cause:
CustomPrivateKeyAlias is not set on the NetworkAccessPointMBean, and must be when the following Custom Identity Key Store attributes are set: CustomIdentityKeyStoreFileName, CustomIdentityKeyStoreType, and either CustomIdentityKeyStorePassPhrase or CustomIdentityKeyStorePassPhraseEncrypted.

Action:
Set the CustomPrivateKeyAlias attribute on the NetworkAccessPointMBean.

BEA-090933
Unable to obtain private key with alias {2} from {1} keystore file : {0}

Category:
Security

Cause:
Either KeyStoreFileName or KeyStorePassPhrase or KeyStoreAlias or KeyStore private key password is incorrect.

Action:
Verify that the path to the keystore, the keystore type, the password for the keystore, the alias for the keystore, and the password for the private key were specified correctly.

BEA-090934
Loading certificates and private key from {1} keystore file {0} caused an Exception :{2}

Category:
Security

Cause:
Either KeyStoreFileName or KeyStorePassPhrase or KeyStoreAlias or KeyStore private key password is incorrect.

Action:
Verify that the path to the keystore, the keystore type, the password for the keystore, the alias for the keystore, and the password for the private key were specified correctly.

BEA-090935
Could not load a {1} keystore from the file {0}. Exception: {2}

Category:
Security

Cause:
There is an I/O or format problem with the keystore data.

Action:
Verify that the path to the keystore, the keystore type, and the password for the keystore were specified correctly. Note that some keystore types (for example, JKS) do not require a password for read-only access. Read the exception text for more help on diagnosing the problem. Reboot the server after correcting the problem.

BEA-090936
Security restarting security realm: {0}

Category:
Security

Cause:
This message is for informational purposes.

Action:
Verify that the correct security realm is being restarted.

BEA-090937
Security completed restarting security realm: {0}

Category:
Security

Cause:
This message is for informational purposes.

Action:
Verify that the correct security realm is restarted.

BEA-090938
Authentication failure: The specified user failed to log in.

Category:
Security

Cause:
The specified username, password, or both are incorrect.

Action:
Verify the username and password.

BEA-090939
The JWTToken is invalid.

Category:
Security

Cause:
JWT token could not satisfy the rule.

Action:
See the log for detailed information and take appropriate action.

BEA-090940
JWTIdentityAsserter received unknown token data, data should by byte[].

Category:
Security

Cause:
An invalid JWT token was supplied.

Action:
Supply a valid JWT token.

BEA-090941
The JWT token cannot pass the sign validation.

Category:
Security

Cause:
An invalid JWT token was supplied.

Action:
Supply a valid JWT token.

BEA-090942
Partitions require a realm with updated default role mapper and authorizations policies. The realm {0} does not contain the correct default policies. Create a new realm and reapply any custom policies.

Category:
Security

Cause:
Partition support requires updated default role mapping and authorization policies.

Action:
Create a new realm with the same providers as the existing realm. Transfer the custom security policies from the old realm to the new realm and set the partition realm attribute to point to the new realm.

BEA-090943
The provider {1} in realm {0} does not support identity domains via the IdentityDomainAwareProviderMBean interface. If identity domains are configured in the domain, then all role mapper, authorization, credential mapper, and audit providers must support this interface.

Category:
Security

Cause:
The configured providers do not support identity domains.

Action:
Ensure that all configured role mapper, authorization, credential mapper, and audit providers support identity domains. Remove any providers that do not support identity domains.

BEA-090944
Inconsistent security configuration, the provider {1} in security realm {0} does not support identity domains via the IdentityDomainAwareProviderMBean interface. If identity domains are configured in the domain, then all role mapper, authorization, credential mapper, and audit providers must support this interface.

Category:
Security

Cause:
The configured providers do not support identity domains.

Action:
Ensure that all configured role mapper, authorization, credential mapper, and audit providers support identity domains. Remove any providers that do not support identity domains.

BEA-090945
Security shutting down retired instance of security realm: {0}

Category:
Security

Cause:
This message is for informational purposes.

Action:
No action is required.

BEA-090946
Security pre-initializing using security realm: {0}

Category:
Security

Cause:
This message is for informational purposes.

Action:
Verify that the correct security realm is configured.

BEA-090947
Security post-initializing using security realm: {0}

Category:
Security

Cause:
This message is for informational purposes.

Action:
Verify that the correct security realm is configured.

BEA-090948
Security starting security realm: {0}

Category:
Security

Cause:
This message is for informational purposes.

Action:
Verify that the correct security realm is being restarted.

BEA-090949
Security completed starting security realm: {0}

Category:
Security

Cause:
This message is for informational purposes.

Action:
Verify that the correct security realm is started.

BEA-090950
The realm "{0}" failed during shut down: {1}.

Category:
Security

Cause:
There are multiple possible causes.

Action:
Carefully read the returned error to determine if any action is required.

BEA-090951
Failed operation using security realm: {0}

Category:
Security

Cause:
There are multiple possible causes.

Action:
Carefully read the returned error to determine if any action is required.

BEA-090952
Provider configured for identity domain(s) "{0}" but login was supplied identity domain {1}

Category:
Security

Cause:
The partition or security configuration may be configured with a different identity domain than the provider.

Action:
None required if the realm handles multiple identity domains. Otherwise, the security configuration may have inconsistent identity domains.

BEA-090953
These configuration changes cannot be activated because the Administrative Identity Domain must be set on the Security Configuration when Identity Domains are in use.

Category:
Security

Cause:
The "Administrative Identity Domain" attribute is not set for the domain's SecurityConfiguration.

Action:
To correct the problem, set the "AdministrativeIdentityDomain" for the domain's SecurityConfiguration.

BEA-090954
These configuration changes cannot be activated because the Primary Identity Domain must be set on Partition {0} when Identity Domains are in use.

Category:
Security

Cause:
The "Primary Identity Domain" attribute is not set for the specified Partition.

Action:
To correct the problem, set the "PrimaryIdentityDomain" for the specified Partition.

BEA-090955
These configuration changes cannot be activated because there is no authenticator configured to support the "{0}" Identity Domain value.

Category:
Security

Cause:
No authenticator in this realm is configured to support the specified Identity Domain value.

Action:
To correct the problem, configure one of the authenticator providers to support the specified identity domain. This can either be a WebLogic Server provider or a custom provider.

BEA-090956
Both permissions.xml and a deployment descriptor grant were found.

Category:
Security

Cause:
Both permissions.xml and a deployment descriptor grant were used to declare permissions.

Action:
Use either permissions.xml or a deployment descriptor grant to declare permissions for the application. Use only one and remove the other before redeployment.

BEA-090957
One or more of the declared permissions in permissions.xml are not allowed.

Category:
Security

Cause:
The application's permissions.xml file contains one or more permissions which are not allowed.

Action:
Remove the prohibited permissions from the permissions.xml file before redeploying the application.

BEA-090958
Security permissions declared in the "{0}" deployment descriptor are not allowed due to the server''s configuration.

Category:
Security

Cause:
The server is configured to not allow Java security permissions to be declared in the Weblogic deployment descriptors.

Action:
Remove Java security permissions from the deployment descriptor or change the server's security configuration before redeployment.

BEA-090959
Java EE packaged permissions are not allowed due to the server"s configuration.

Category:
Security

Cause:
The server is configured to not allow Java EE packaged permissions in the application.

Action:
Remove permissions.xml or change the server's security configuration before redeployment.

BEA-090960
The serverr"s SSL configuration is not available. There will potentially be SSL handshake failures.

Category:
Security

Cause:
The server has not been able to load its SSL configuration. This usually occurs early in server startup, before Management Service runtime access is available.

Action:
Verify that the Administration Server is running. If the Administration Server non-secure port is disabled, verify that the Managed Server default SSL configuration is sufficient to handshake with the Administration Server over the SSL port.

BEA-090961
These configuration changes cannot be activated because the realm "{0}" already exists.

Category:
Security

Cause:
There is more than one realm named "{0}" configured for the domain's SecurityConfiguration.

Action:
To correct the problem, change the name of each realm configured for the domain's SecurityConfiguration to be a unique name.

BEA-090962
These configuration changes cannot be activated because the realm "{0}" is not valid.

Category:
Security

Cause:
The realm "{0}" is not properly configured for the domain's SecurityConfiguration. See the nested exceptions that accompany this error for details.

Action:
To correct the problem, review and address the nested exceptions that accompany this error.

BEA-090963
The {0} provider imports a modified entry: {1}

Category:
Security

Cause:
The security provider needs to be modified because of the overwrite flag is open.

Action:
Modified the imported data from the existing one.

BEA-090964
The connection to the datasource using "{0}" could not be established due to the following error: {1}.

Category:
Security

Cause:
There are multiple possible causes.

Action:
Read the returned exception to determine if any action is required.

BEA-090965
Unable to create policy with type {0}. Got exception {1}.

Category:
Security

Cause:
An internal WebLogic server error occurred when creating policy type {0}.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-090966
A failure has occurred checking for WebLogic Kernel Permission: {0}

Category:
Security

Cause:
An attempt to perform an action that requires privileges has failed.

Action:
Read the returned exception to determine what action is required.

BEA-090967
LDAP test connection failed: {0} not configured.

Category:
Security

Cause:
The connection parameters provided were incomplete.

Action:
Verify that the connection parameters provided are complete.

BEA-090968
Error processing test connection parameters {0}: {1}

Category:
Security

Cause:
The connection parameters provided were incorrect.

Action:
Verify that the connection parameters provided are correct.

BEA-090969
Identity Assertion type cannot be null

Category:
Security

Cause:
The token type was null.

Action:
Null should not be passed as the token type.

BEA-090970
Identity Assertion token cannot be null

Category:
Security

Cause:
The identity assertion token was null.

Action:
Null should not be passed as the token.

BEA-090971
Identity Assertion type of {0} is not a valid token type for the OpenID Connect Identity Assertion provider.

Category:
Security

Cause:
The token type passed in did not match the OpenID Connect Identity Assertion token type.

Action:
Pass in the correct token type for the OpenID Connect Identity Assertion provider.

BEA-090972
Resource type already registered: "{0}"

Category:
Security

Cause:
The supplied resource type has already been registered.

Action:
Specify a valid resource type.

BEA-090973
Ldap request wait exceeds time limit {0} milliseconds, try number count {1}

Category:
Security

Cause:
Ldap request takes unexpected long time.

Action:
None required. Otherwise check if the Ldap authentication provider configuration is optimized or Ldap server issue.

BEA-090974
File does not exist {0}

Category:
Security

Cause:
SerializedSystemIni.dat does not exist in the specified location.

Action:
Create a SerializedSystemIni.dat in the specified location if needed.

BEA-090975
The connection between the WebLogic servers cannot be authorized since the nonce value has expired. Verify that clock skew has not occurred between the servers in the domain.

Category:
Security

Cause:
Clock skew between the two servers may cause the client nonce to be expired when it is validated on the server.

Action:
Verify that the clocks on the servers in the domain are in agreement. Optionally, enable the Network Time Protocol daemon on the servers in the domain.

BEA-090976
Secure Mode is enabled but no auditing provider is configured in realm: {0}.

Category:
Security

Cause:
Secure Mode is enabled but no auditing provider is configured.

Action:
None required otherwise set SecureModeMBean WarnOnAuditing to false to avoid this message.

BEA-090977
Secure Mode is enabled but the Default Auditor logging level does not include WARNING, ERROR, and FAILURE audit records in realm: {0}.

Category:
Security

Cause:
Secure Mode is enabled but the Default Auditor logging level does not include WARNING, ERROR, and FAILURE audit records.

Action:
None required otherwise set SecureModeMBean WarnOnAuditing to false to avoid this message.

BEA-090978
Secure Mode is enabled but user lockout settings are not secure in realm: {0}, i.e. LockoutThreshold should not be greater than 5, LockoutDuration should not be less than 30.

Category:
Security

Cause:
Secure Mode is enabled but user lockout is not enabled or lockout settings are less restrictive than default.

Action:
This is a warning message, no action is required.

BEA-090979
Secure Mode is enabled but unencrypted password is used in command line, i.e. system property weblogic.management.password is set.

Category:
Security

Cause:
Secure Mode is enabled but unencrypted password is used in command line.

Action:
This is a warning message, no action is required.

BEA-090980
Secure Mode is enabled but no password validator is configured in realm: {0}.

Category:
Security

Cause:
Secure Mode is enabled but no password validator is configured.

Action:
This is a warning message, no action is required.

BEA-090981
Secure Mode is enabled but the Security Manager is not enabled.

Category:
Security

Cause:
Secure Mode is enabled but the Security Manager is not enabled.

Action:
None required otherwise set SecureModeMBean WarnOnJavaSecurityManager to false to avoid this message.

BEA-090982
Secure Mode is enabled but PostBind is not enabled for machine : {0} when unix machine is configured and port {1} < 1024 is used.

Category:
Security

Cause:
Secure Mode is enabled but PostBind is not enabled when unix machine is configured and port < 1024 is used.

Action:
This is a warning message, no action is required.

BEA-090983
Secure Mode is enabled but the the administration port is not enabled.

Category:
Security

Cause:
Secure Mode is enabled but the the administration port is not enabled.

Action:
This is a warning message, no action is required.

BEA-090984
Secure Mode is enabled but the fie or directory {0} owner {1} does not match the domain directory owner {2}.

Category:
Security

Cause:
Secure Mode is enabled but the file or directory owner does not match the domain directory owner.

Action:
None required otherwise set SecureModeMBean WarnOnInsecureFileSystem to false to avoid this message.

BEA-090985
Secure Mode is enabled but the the file or directory {0} is insecure since its permission is not a minimum of umask 027.

Category:
Security

Cause:
Secure Mode is enabled but the the file or directory permission is insecure.

Action:
None required otherwise change the file or directory permission to be a minimum of umask 027, or set SecureModeMBean WarnOnInsecureFileSystem to false to avoid this message.

BEA-090986
Secure Mode requires a realm with updated default authorizations policies. The realm {0} does not contain the correct default policies. Create a new realm and reapply any custom policies.

Category:
Security

Cause:
Secure Mode support requires updated default authorization policies.

Action:
Create a new realm with the same providers as the existing realm. Transfer the custom security policies from the old realm to the new realm and set the realm attribute to point to the new realm.

BEA-090987
SSLv3 is enabled by the system property {0} in secure mode. SSLv3 is vulnerable and should not be enabled.

Category:
Security

Cause:
SSLv3 is enabled by the system property in secure mode.

Action:
Enable a secure TLS version such as TLSv1.2 or turn off warning on insecure SSL configuration in secure mode.

BEA-090988
Basic Constraints extension validation is turned off by the system property {0}=off in secure mode.

Category:
Security

Cause:
Basic Constraints extension validation is turned off by the system property {0}=off in secure mode.

Action:
Turn on Basic Constraints extension validation, {0}=strong or {0}=true or {0}=strict, or turn off warning on insecure SSL configuration in secure mode.

BEA-090989
SSL hostname verification is disabled by the system property {0} in secure mode.

Category:
Security

Cause:
SSL hostname verification is disabled by the system property {0} in secure mode.

Action:
Enable SSL host name verification or turn off warning on insecure SSL configuration in secure mode.

BEA-090990
SSL hostname verification is disabled by the SSL configuration of server {0} in secure mode.

Category:
Security

Cause:
SSL hostname verification is disabled by the SSL configuration of server {0} in secure mode.

Action:
Enable SSL host name verification or turn off warning on insecure SSL configuration in secure mode.

BEA-090991
SSL hostname verification is disabled by the SSL configuration of server channel {0} in secure mode.

Category:
Security

Cause:
SSL hostname verification is disabled by the SSL configuration of server channel {0} in secure mode.

Action:
Enable SSL host name verification or turn off warning on insecure SSL configuration in secure mode.

BEA-090992
SSLv3 is enabled as the minimum TLS protocol version by the system property {0} in secure mode.

Category:
Security

Cause:
SSLv3 is enabled as the minimum TLS protocol version by the system property {0} in secure mode.

Action:
Configure a secure TLS version such as TLSv1.2 as the minimum TLS protocol version or turn off warning on insecure SSL configuration in secure mode.

BEA-090993
SSLv3 is enabled as the minimum TLS protocol version by the SSL configuration of server {0} in secure mode.

Category:
Security

Cause:
SSLv3 is enabled as the minimum TLS protocol version by the SSL configuration of server {0} in secure mode.

Action:
Configure a secure TLS version such as TLSv1.2 as the minimum TLS protocol version or turn off warning on insecure SSL configuration in secure mode.

BEA-090994
SSLv3 is enabled as the minimum TLS protocol version by the SSL configuration of server channel {0} in secure mode.

Category:
Security

Cause:
SSLv3 is enabled as the minimum TLS protocol version by the SSL configuration of server channel {0} in secure mode.

Action:
Configure a secure TLS version such as TLSv1.2 as the minimum TLS protocol version or turn off warning on insecure SSL configuration in secure mode.

BEA-090995
Null cipher suites are allowed by the system property {0} in secure mode.

Category:
Security

Cause:
Null cipher suites are allowed by the system property {0} in secure mode.

Action:
Null cipher suites are not secure and should not be allowed or turn off warning on insecure SSL configuration in secure mode.

BEA-090996
Null cipher suites are allowed by the SSL configuration of server {0} in secure mode.

Category:
Security

Cause:
Null cipher suites are allowed by the SSL configuration of server {0} in secure mode.

Action:
Null cipher suites are not secure and should not be allowed or turn off warning on insecure SSL configuration in secure mode.

BEA-090997
Null cipher suites are allowed by the SSL configuration of server channel {0} in secure mode.

Category:
Security

Cause:
Null cipher suites are allowed by the SSL configuration of server channel {0} in secure mode.

Action:
Null cipher suites are not secure and should not be allowed or turn off warning on insecure SSL configuration in secure mode.

BEA-090998
Anonymous cipher suites are allowed by the system property {0} in secure mode.

Category:
Security

Cause:
Anonymous cipher suites are allowed by the system property {0} in secure mode.

Action:
Anonymous cipher suites are not secure and should not be allowed or turn off warning on insecure SSL configuration in secure mode.

BEA-090999
TLS client initiated secure renegotation is enabled by the SSL configuration of server {0} in secure mode.

Category:
Security

Cause:
TLS client initiated secure renegotation is enabled by the SSL configuration of server {0} in secure mode.

Action:
Disable TLS client initiated secure renegotation or turn off warning on insecure SSL configuration in secure mode.

BEA-091000
TLS client initiated secure renegotation is enabled by the SSL configuration of server channel {0} in secure mode.

Category:
Security

Cause:
TLS client initiated secure renegotation is enabled by the SSL configuration of server channel {0} in secure mode.

Action:
Disable TLS client initiated secure renegotation or turn off warning on insecure SSL configuration in secure mode.

BEA-091001
Insecure cipher suites are configured by the SSL configuration of server {0} in secure mode: {1}

Category:
Security

Cause:
Insecure cipher suites are configured for secure mode.

Action:
Remove the insecure cipher suites {1} or turn off warning on insecure SSL configuration in secure mode.

BEA-091002
Insecure cipher suites are configured by the SSL configuration of server channel {0} in secure mode: {1}.

Category:
Security

Cause:
Insecure cipher suites are configured for secure mode.

Action:
Remove the insecure cipher suites {1} or turn off warning on insecure SSL configuration in secure mode.

BEA-091003
Secure Mode requires that users in the Administrators group do not have obvious user names. Change the user name "{0}" so it is not a commonly used administrator name.

Category:
Security

Cause:
A user that is a member of the Administrators group has an obvious user name.

Action:
Change the user name to non-obvious name.

BEA-091004
Secure Mode requires that the samples are not installed in the WebLogic installation directory.

Category:
Security

Cause:
The WebLogic installation contains the samples directory

Action:
Reinstall WebLogic and do not include the samples when choosing the installation type.

BEA-091005
Boot authentication attempt failed. Retry attempt {0} of {1}

Category:
Security

Cause:
The authentication for the boot user failed.

Action:
Wait until the server fails to boot and determine if the authentication failure can be corrected. If so, then retry the boot after correcting the authentication failure.

BEA-091006
The WLS SSL-ALPN jars are not found in java.endorsed.dirs directory. The HTTP/2 over SSL (h2) protocol will not be supported.

Category:
Security

Cause:
WLS can't find SSL-ALPN related classes because WLS SSL-ALPN related jars are not found in java.endorsed.dirs directory.

Action:
Check the system property java.endorsed.dirs is configured and make sure WLS SSL-ALPN jars are in the directory.

BEA-091007
The Oracle Identity Cloud Service returned '{0}' 429 status code responses (Too Many Requests) in the last '{1}' seconds.

Category:
Security

Cause:
The Oracle Identity Cloud Service response indicating user has sent too many reqests in a given amount of time.

Action:
No action is required.

BEA-091008
The Oracle Identity Cloud Service returned '{0}' service unavailable or network timeout responses in the last '{1}' seconds.

Category:
Security

Cause:
The Oracle Identity Cloud Service unavailable or timeout caused by network issue or other issues.

Action:
Verify that the network or the Oracle Identity Cloud Service is not experiencing issues.

BEA-096500
Artifact of type SAML2 artifact-04 is not successfully constructed.

Category:
Security

Cause:
The passing parameter {0} was null or its length was not {1}.

Action:
Check the parameters being passed to the SAMLArtifact constructor.

BEA-096501
SAML message returned in samlp:ArtifactResponse is not the right type. It should be of {0} type.

Category:
Security

Cause:
The SAML message that was returned in samlp:ArtifactResponse was not the one that samlp:ArtifactRequest requested.

Action:
Check the remote ARS storage to see if there is a {0} corresponding to the artifact.

BEA-096502
There is no SAML message in returned samlp:ArtifactResponse.

Category:
Security

Cause:
The SAML message may have been deleted because of expiration, or the client has no authority to access it.

Action:
Check the remote ARS storage to see if there is an item corresponding to the artifact.

BEA-096503
The artifact in the HTTP request is null. It should be {0} parameter in the HTTP request.

Category:
Security

Cause:
The artifact in the HTTP request was null. It should be {0} parameter in the HTTP request.

Action:
Check the HTTP request to see if there is a {0} parameter with a non-null value.

BEA-096504
Could not get binding handler of {0} type.

Category:
Security

Cause:
An internal WebLogic Server error occurred while getting the binding handler.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-096505
Could not get SAML response, it should be of {0} type.

Category:
Security

Cause:
The remote service may be down or the message exchange timed out.

Action:
Check the remote service status.

BEA-096506
The SAML response is invalid in the field {0}, expected value is {1}, actual value is {2}.

Category:
Security

Cause:
The SAML response was not the one that the SAML request expected.

Action:
Check the remote service configuration.

BEA-096507
Could not get end point, the entityID is {0}, service type is {1}, end point index is {2}.

Category:
Security

Cause:
The end point was not registered.

Action:
Check the register storage to see if there is such an endpoint.

BEA-096508
Cannot get the key to sign {0}.

Category:
Security

Cause:
There may not be a key to sign {0}.

Action:
Check the local configuration to see if there is a key for signing {0}.

BEA-096509
Cannot get the key to verify the signature of {0}.

Category:
Security

Cause:
There may not be a key to verify the signature of {0}.

Action:
Check the partner registration information to see if there is key for verifying {0}.

BEA-096510
There is no SAML message in the HTTP request, it should be a value of {0} parameter.

Category:
Security

Cause:
There was no message in the HTTP request with a value of {0}.

Action:
Check the HTTP request to confirm that there is a parameter with a non-null value.

BEA-096511
The certificate chain sent by the SSL server is null or empty.

Category:
Security

Cause:
The remote partner acting as an SSL server did not send a certificate to authenticate itself.

Action:
Check the remote partner to see if it has an SSL certificate to authenticate itself.

BEA-096512
The SSL server cannot be trusted for {0}.

Category:
Security

Cause:
The remote partner acting as an SSL server cannot be trusted.

Action:
Check the SSL certificate that the remote partner uses to authenticate itself.

BEA-096513
Could not get partner, the entityID(or SHA-1 hash value) is {0}.

Category:
Security

Cause:
The partner is not registered.

Action:
Check the register storage to see if there is such a partner.

BEA-096514
Could not get Transport Layer Certificate from partner whose entityId is {0}.

Category:
Security

Cause:
The partner did not register its Transport Layer Certificate information.

Action:
Check the register storage to see if this partner has a Transport Layer Certificate.

BEA-096515
The SSL client is expected to authenticate, but cannot get the key and certificate.

Category:
Security

Cause:
The SSL key and certificate could not be retrieved.

Action:
Check the metadata to see if there is a Transport Layer Certificate and key.

BEA-096516
Could not get SAML signature from the HTTP request, it should be a {0} parameter.

Category:
Security

Cause:
If there is no SAML signature in the HTTP request, there should also be no signature algorithm in the HTTP request.

Action:
Check the HTTP request. The signature and signature algorithm should appear at the same time.

BEA-096517
The SAML message was signed but could not get a signature from it.

Category:
Security

Cause:
The SAML message was signed but there was no signature to retrieve.

Action:
Check the SAML message for the signature.

BEA-096518
The signature is invalid.

Category:
Security

Cause:
The signature was verified but was not valid.

Action:
Provide a valid signature.

BEA-096519
Could not get artifact when storing the SAML message, have no idea whether the SAML message was stored successfully.

Category:
Security

Cause:
There may have been an error when generating the artifact.

Action:
Check the log files for an error.

BEA-096520
Could not receive a valid SAML request of type "{0}" from HTTP request.

Category:
Security

Cause:
A valid SAML request of type "{0}" was not received from the HTTP request.

Action:
Check whether the configuration of the corresponding partner is correct.

BEA-096521
Could not receive a valid SAML response of type "{0}" from HTTP request.

Category:
Security

Cause:
A valid SAML response of type "{0}" was not retrieved from the HTTP request.

Action:
Check whether the configuration of the corresponding partner is correct.

BEA-096522
Error occurs when signing {0}.

Category:
Security

Cause:
Error occurs when signing {0}.

Action:
Error occurs when signing {0}.

BEA-096523
Authentication failed.

Category:
Security

Cause:
Authentication failed due to an invalid certificate or an invalid username or password.

Action:
Ensure that your certificate or your username and password are correct.

BEA-096524
Invalid Identity Assertion token object for specified token type.

Category:
Security

Cause:
An internal WebLogic server error occurred while determining the token type.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-096525
Signature required but assertion is not signed.

Category:
Security

Cause:
An unsigned SAML assertion was received where the SAML configuration required a signed assertion.

Action:
Check the SAML partner configuration or contact the SAML Identity Provider.

BEA-096526
There must be a subject in assertion.

Category:
Security

Cause:
A SAML assertion was received in which the SAML Subject was not provided.

Action:
Contact the SAML Identity Provider for information on how to correct the problem.

BEA-096527
No SubjectConfirmation in assertion.

Category:
Security

Cause:
A SAML assertion was received in which the SAML Subject Confirmation was not provided.

Action:
Contact the SAML Identity Provider for information on how to correct the problem.

BEA-096528
Unsupported assertion type: {0}.

Category:
Security

Cause:
A SAML assertion was received in which the SAML Subject Confirmation is not supported.

Action:
Contact the SAML Identity Provider for information on how to correct the problem.

BEA-096529
Signature required but no valid certificate in the specified partner configuration.

Category:
Security

Cause:
A signature was required but the certificate has expired, is not yet valid or is undefined in the specified partner configuration.

Action:
Provide a valid certificate for the partner.

BEA-096530
Cannot get the key to verify the signature.

Category:
Security

Cause:
An improper key was provided.

Action:
Provide a proper key to verify the signature.

BEA-096531
The signature is invalid.

Category:
Security

Cause:
The signature was verified but was not valid.

Action:
Provide a valid signature.

BEA-096532
Invalid version found in the {0} document: {1}.

Category:
Security

Cause:
The sender sent a document that is not version 2.0.

Action:
Fix the SAML sender.

BEA-096533
Certificate in assertion''s keyinfo does not match configured signing certificate.

Category:
Security

Cause:
A SAML assertion was received where the SAML KeyInfo does not match the SAML partner entry.

Action:
Check the SAML partner configuration or contact the SAML Identity Provider.

BEA-096534
No issuer in the assertion.

Category:
Security

Cause:
A SAML assertion was received where the SAML Issuer is not supplied or the SAML Issuer is empty.

Action:
Contact the SAML Identity Provider for information on how to correct the problem.

BEA-096535
The Issuer in {0} is invalid: {1}.

Category:
Security

Cause:
The sender sent an invalid SAML document that contains an invalid Issuer URI.

Action:
Ask the SAML requester to fix this problem.

BEA-096536
Invalid issuer format: {0}.

Category:
Security

Cause:
The sender sent a document that contains an invalid issuer format attribute.

Action:
Ask the SAML requester to send a correct document.

BEA-096537
Assertion is not yet valid ({0} condition).

Category:
Security

Cause:
The received SAML assertion is not yet valid.

Action:
Check the SAML configuration, the system clock or contact the SAML Identity Provider.

BEA-096538
Assertion has expired ({0} condition).

Category:
Security

Cause:
The received SAML assertion has expired.

Action:
Check the SAML configuration, the system clock or contact the SAML Identity Provider.

BEA-096539
AudienceRestriction condition not satisfied (no matching audience).

Category:
Security

Cause:
The received SAML assertion audience restrictions where not satisfied.

Action:
Check the SAML partner configuration or contact the SAML Identity Provider.

BEA-096540
The assertion: {0} cannot be used again.

Category:
Security

Cause:
The received SAML assertion has already been consumed and cannot be used again.

Action:
Contact the SAML Identity Provider for information on how to correct the problem.

BEA-096541
Web SSO profile must be bearer confirmation method.

Category:
Security

Cause:
A SAML assertion was received where the SAML Subject Confirmation must be of Bearer type.

Action:
Contact the SAML Identity Provider for information on how to correct the problem.

BEA-096542
No NameID in assertion.

Category:
Security

Cause:
A SAML assertion was received in which the SAML Issuer is not supplied or the SAML Issuer is empty.

Action:
Contact the SAML Identity Provider for information on how to correct the problem.

BEA-096543
The partner: {0} does not exist or is disabled.

Category:
Security

Cause:
The partner: {0} does not exist or is disabled.

Action:
Register or enable the specified partner.

BEA-096544
Cannot find identity provider partner, partnerName: {0}, request URI: {1}.

Category:
Security

Cause:
Cannot find identity provider partner, partnerName: {0}, request URI: {1}.

Action:
Check the identity provider partner setting.

BEA-096545
Cannot find single sign-on services for partner: {0}.

Category:
Security

Cause:
No single sign-on services are defined for partner: {0}.

Action:
Define single sign-on services for partner: {0}.

BEA-096546
Cannot get the single sign-on sign key to sign the {0} in the key store.

Category:
Security

Cause:
Either no single sign-on sign key is defined in the local configuration or the key/keystore is invalid.

Action:
Correct the key configuration for SAML services.

BEA-096547
The status code of SAML2 response indicates that the request failed: {0}.

Category:
Security

Cause:
The SAML2 response from the identity provider partner indicates that the request failed.

Action:
Contact the identity provider partner to get the reason.

BEA-096548
Cannot find identity provider partner for issuer URI: {0}.

Category:
Security

Cause:
The identity provider partner for issuer URI: {0} is not defined.

Action:
Define the identity provider partner for issuer URI: {0}.

BEA-096549
Cannot get a valid certificate in partner registry to verify {0} for partner {1}.

Category:
Security

Cause:
The certificate has expired, is not yet valid or is undefined for the specified partner.

Action:
Provide a valid certificate for the partner.

BEA-096550
Failed to create session for identity: {0}.

Category:
Security

Cause:
This usually is caused by one of the LoginSessionListeners failing to create a session.

Action:
Ensure that all the listeners work properly or try to re-install.

BEA-096551
{0} binding of local configuration is not enabled.

Category:
Security

Cause:
The binding: {0} of the local configuration is not enabled.

Action:
Enable the binding: {0} for the local configuration.

BEA-096552
Illegal destination: {0} of assertion response.

Category:
Security

Cause:
The SAML2 response received from the identity provider partner is illegal.

Action:
Contact the identity provider partner to ensure that the generated response is correct.

BEA-096554
Cannot find request for InResponseTo: {0} in response.

Category:
Security

Cause:
The SAML2 response received from the identity provider partner is illegal.

Action:
Contact the identity provider partner to ensure that the generated response is correct.

BEA-096555
Attribute: {0} should not be empty.

Category:
Security

Cause:
The SAML2 response received from the identity provider partner is illegal.

Action:
Contact the identity provider partner to ensure that the generated response is correct.

BEA-096556
Attribute: {0} should be omitted.

Category:
Security

Cause:
The SAML2 response received from the identity provider partner is illegal.

Action:
Contact the identity provider partner to ensure that the generated response is correct.

BEA-096557
Illegal confirmation method: {0}.

Category:
Security

Cause:
The SAML2 response received from the identity provider partner is illegal.

Action:
Contact the identity provider partner to ensure that the generated response is correct.

BEA-096558
Illegal Recipient: {0} for the subject confirmation data.

Category:
Security

Cause:
The SAML2 response received from the identity provider partner is illegal.

Action:
Contact the identity provider partner to ensure that the generated response is correct.

BEA-096559
Illegal InResponseTo: {0} for the subject confirmation.

Category:
Security

Cause:
The SAML2 response received from the identity provider partner is illegal.

Action:
Contact the identity provider partner to ensure that the generated response is correct.

BEA-096560
The Issuer element cannot have NameQualifier, SPNameQualifer and SPProviderID.

Category:
Security

Cause:
The SAML requester sent a document that contains an invalid <Issuer>.

Action:
Ask the SAML Requester to fix this.

BEA-096561
Identity provider partner: {0} is not enabled.

Category:
Security

Cause:
The specified identity provider partner is not enabled.

Action:
Enable the identity provider partner.

BEA-096562
Errors occurred when sending {0}.

Category:
Security

Cause:
An internal WebLogic server error occurred when sending A SAML assertion.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-096563
Errors occurred when receiving {0}.

Category:
Security

Cause:
An internal WebLogic Server error occurred when A SAML assertion was requested.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-096565
Artifact requester authentication failed.

Category:
Security

Cause:
There was an invalid basic auth/certificate.

Action:
Check the log for more details and take appropriate action.

BEA-096566
The SAML2 identity provider service is disabled.

Category:
Security

Cause:
The SAML2 identity provider service is disabled in the local configuration, but a request was sent to this service.

Action:
Enable the identity provider in the local configuration.

BEA-096567
Cannot find service provider partner with the specified URI {0}.

Category:
Security

Cause:
The partner may be misconfigured in the partner registry, or this issuer is not enabled/configured in the registry.

Action:
Configure the partner correctly in the partner registry, or just ignore it if this issuer should not be served. It could also be errors in the service provider that issues this request.

BEA-096568
The service provider partner {0} is disabled.

Category:
Security

Cause:
The specified service provider partner is disabled in the partner registry.

Action:
Enable the partner in the partner registry.

BEA-096569
Cannot authenticate user in passive mode.

Category:
Security

Cause:
The AuthnRequest wants the user to be authenticated in passive mode, but the Identity Provider is not able to do this.

Action:
Ensure that the service provider does not send passive requests, or just ignore this error.

BEA-096570
The user is accessing the login return URL of SAML2 service, however, this user is not authenticated.

Category:
Security

Cause:
A user accidentally accessed this page or bookmarked it, or the login application is behaving incorrectly.

Action:
Fix the login application.

BEA-096571
There is no <AuthnRequest> object in user"s session.

Category:
Security

Cause:
The user's session may have expired. The user must do the single sign-on process from the very beginning. This could also be caused by an incorrect login application.

Action:
Start the single sign-on process from the beginning, or fix the login application.

BEA-096572
The user is accessing the Identity Provider initiator service, but is not authenticated yet.

Category:
Security

Cause:
The user accidentally accessed this page or bookmarked it, or the login application is behaving incorrectly.

Action:
Fix the login application or the page links to this URL.

BEA-096573
The Identity provider-initiated single sign-on requires a parameter {0}, but the request does not have one.

Category:
Security

Cause:
The user or the link did not append the parameter.

Action:
Append the parameter in the request.

BEA-096574
Cannot find partner with name: {0}

Category:
Security

Cause:
The partner with name {0} does not exist in the partner registry.

Action:
Add a partner with the indicated name, or rename a partner to this name.

BEA-096575
The URL for relay state is too long.

Category:
Security

Cause:
The service provider-initiated single sign-on requester sent a request URL longer than 80 bytes.

Action:
If the URL for the service provider is too long, do not send it.

BEA-096576
Received a SAML document that is not a AuthnRequest document, but {0}.

Category:
Security

Cause:
The SAML requester sent an invalid document to the identity provider single sign-on service.

Action:
Ask the requester to send a valid document.

BEA-096577
Failed to receive {0} document from the requester.

Category:
Security

Cause:
Review other messages in the log for the cause.

Action:
Fix the error in the document or network.

BEA-096578
Cannot generate assertion for the user.

Category:
Security

Cause:
There may be an error in the credential mapper, or the SAML2 credential mapper is not configured correctly.

Action:
Configure the SAML2 credential mapper correctly.

BEA-096579
Failed to unmarshal the assertion from the credential mapper.

Category:
Security

Cause:
An internal WebLogic Server error occurred during unmarshaling.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-096580
No assertion consumer services configured in the {0} partner.

Category:
Security

Cause:
No assertion consumer services are configured in the partner.

Action:
Configure the ACS service for this partner.

BEA-096581
The destination attribute of <AuthnRequest> does not match local configuration.

Category:
Security

Cause:
Either the request was sent to the wrong place, or the request document is wrong.

Action:
Fix the SAML requester to match the destination attribute.

BEA-096582
<SubjectConfirmation> cannot exist in the <Subject> element of <AuthnRequest>

Category:
Security

Cause:
The SAML requester sent an <AuthnRequest>, its <subject> contains a <SubjectConfirmation>, which is not allowed by the SAML specification.

Action:
Fix the SAML requester.

BEA-096583
Requested NameId format not supported, only urn:oasis:names:tc:SAML:1.1:nameid-format:unspecified is supported.

Category:
Security

Cause:
The SAML requester sent a request that is not supported yet.

Action:
Fix the SAML requester to send a request without the name id format, or set the format to "unspecified".

BEA-096584
<RequestedAuthnContext> is not currently supported.

Category:
Security

Cause:
The SAML requester sent an invalid <AuthnRequest> document.

Action:
Fix the SAML requester to send a request without <RequestedAuthnContext>.

BEA-096585
The SPNameQualifier is not supported in <AuthnRequest>.

Category:
Security

Cause:
The SAML requester sent a request that is not supported yet.

Action:
Fix the SAML requester to not send such a document.

BEA-096586
Find service provider partner by issuer URI {0} error.

Category:
Security

Cause:
The exception was caused while searching for the service provider partner from the store by the issuer uri.

Action:
Check the store service.

BEA-096587
Find service provider partner by name {0} error.

Category:
Security

Cause:
This exception was caused while searching for the service provider partner from the store by name.

Action:
Check the store service.

BEA-096588
Find identity provider partner by name {0} error.

Category:
Security

Cause:
This exception was caused while searching for the identity provider partner from the store by name.

Action:
Check the store service.

BEA-096589
Find partner by name {0} error.

Category:
Security

Cause:
This exception was caused while searching for the partner from the store by name.

Action:
Check the store service.

BEA-096590
Could not get local entity ID for checking audience in assertion.

Category:
Security

Cause:
The service provider has no entity ID.

Action:
Check the service provider local configuration to see whether it has an entity ID.

BEA-096591
Could not get partner from partner registry by name.

Category:
Security

Cause:
There is no such partner in the partner registry.

Action:
Check the partner registry to see whether this partner exists.

BEA-096592
Partner is not enabled in partner registry.

Category:
Security

Cause:
This partner is in the partner registry, but the partner is not enabled.

Action:
Check the partner registry to see whether the partner is enabled.

BEA-096593
Audience cannot be empty.

Category:
Security

Cause:
The assertion contains an empty audience.

Action:
Check the CredentialMapper.

BEA-096594
Web single sign-on service provider partner entity ID is empty, could not create assertion.

Category:
Security

Cause:
The SAML partner entry does not have an Entity ID or the Entity ID is empty.

Action:
Check and import the SAML service provider metadata file or contact the SAML service provider to obtain the Entity ID.

BEA-096595
Confirmation method should not be empty.

Category:
Security

Cause:
The provider partner has no confirmation method.

Action:
Check the partner information to make sure it has a confirmation method.

BEA-096596
Assertion signing certificate should not be empty while wantAssertionSigned is TRUE.

Category:
Security

Cause:
The provider partner has no assertion signing certificate while wantAssertionSigned is TRUE.

Action:
Check the partner information to make sure it has an assertion signing certificate.

BEA-096597
Artifact POST form should not be empty while isArtifactUsePost is TRUE.

Category:
Security

Cause:
The provider partner has no artifact POST form while isArtifactUsePost is TRUE.

Action:
Check the partner information to make sure it has an artifact POST form.

BEA-096598
Single sign-on signing certificate should not be empty while assertion/artifact request/authn request wants to be signed.

Category:
Security

Cause:
The provider partner has no single sign-on signing certificate while the assertion/artifact request/authn request wants to be signed.

Action:
Check the partner information to make sure it has a single sign-on signing certificate.

BEA-096599
Issuer URI should not be empty.

Category:
Security

Cause:
The provider partner has no issuer URI.

Action:
Check the partner information to make sure it has an issuer URI.

BEA-096600
No SAML2 service entity ID configured.

Category:
Security

Cause:
The SAML2 service entity ID is not configured.

Action:
Configure the SAML2 service entity ID.

BEA-096601
No SAML2 service published site URL configured.

Category:
Security

Cause:
The SAML2 service published site URL is not configured.

Action:
Configure the SAML2 service published site URL.

BEA-096602
No SAML2 service single sign-on signing key alias configured.

Category:
Security

Cause:
The SAML2 service single sign-on signing key alias is not configured.

Action:
Configure a SAML2 service single sign-on signing key alias.

BEA-096603
No SAML2 service single sign-on signing key pass phrase configured.

Category:
Security

Cause:
The SAML2 service single sign-on signing key pass phrase is not configured.

Action:
Configure the SAML2 service single sign-on signing key pass phrase.

BEA-096604
No SAML2 service login return query parameter are configured.

Category:
Security

Cause:
The SAML2 service login return query parameter is not configured.

Action:
Configure the SAML2 service login return query parameter.

BEA-096605
Entity ID should not be empty.

Category:
Security

Cause:
The provider partner has no entity ID.

Action:
Check the partner information to make sure it has an entity ID.

BEA-096606
Name should not be empty.

Category:
Security

Cause:
The provider partner has no name.

Action:
Check the partner information to make sure it has a name.

BEA-096607
Single sign-on services should not be empty.

Category:
Security

Cause:
Provider partner has no single sign-on services.

Action:
Check the partner information to make sure it has single sign-on services.

BEA-096608
Assertion consumer services should not be empty.

Category:
Security

Cause:
The provider partner has no assertion consumer services.

Action:
Check the partner information to make sure it has assertion consumer services.

BEA-096609
Illegal published site url: {0}.

Category:
Security

Cause:
The published site url is illegal.

Action:
Check the partner information to make sure it has a legal published site url.

BEA-096610
Cannot resolve IssuerURI for SAML Assertion.

Category:
Security

Cause:
The system could not resolve the IssuerURI for the SAML Assertion from the context and credential mapper MBean.

Action:
Check the context and credential mapper MBean to make sure that the issuerURI is not empty.

BEA-096611
Cannot get key info for key {0} from key service.

Category:
Security

Cause:
The key info got from key service for key {0} is empty.

Action:
Check the key store service for key {0}.

BEA-096612
Decrypt password {0} error.

Category:
Security

Cause:
The password {0} could not be decrypted, causing an exception.

Action:
Check the key and the password.

BEA-096613
Clearing cache {0}.

Category:
Security

Cause:
The SAML cache is being cleared.

Action:
No action is required.

BEA-096614
Cache {0} cleared.

Category:
Security

Cause:
The SAML cache has been cleared.

Action:
No action is required.

BEA-096615
The SAML credential cache item"s ttl value {0} is smaller than the minimum viable ttl {1} in milliseconds and will not be cached.

Category:
Security

Cause:
The SAML credential cache is unable to retain the item due to the length of the timeout.

Action:
No action is required.

BEA-096616
The value of max to return is negative.

Category:
Security

Cause:
The value of max to return cannot be negative.

Action:
Check the value of max to return and make sure that the value is not negative.

BEA-096617
The value for contact person type is illegal.

Category:
Security

Cause:
The value for the contact person type is not legal. The legal value must be in one of "technical", "support", "administrative", "billing" or "other".

Action:
Choose one of the legal values and try again.

BEA-096618
Invalid keystore configuration.

Category:
Security

Cause:
The keystore configuration is not correct.

Action:
Configure a valid value and try again.

BEA-096619
Key name is null or empty.

Category:
Security

Cause:
The key name is null or empty when updating/retrieving key information.

Action:
Choose a valid key name and try again.

BEA-096620
Invalid key information.

Category:
Security

Cause:
At least one of key name, alias or passphrase is not correct.

Action:
Choose a valid value and try again.

BEA-096621
SAML2 Service cannot be initialized:{0}

Category:
Security

Cause:
Errors occurred while initializing the SAML2 service.

Action:
Check and change the SAML2 configuration and try again.

BEA-096622
ForceAuthn and IsPassive cannot both be true.

Category:
Security

Cause:
ForceAuthn wants to authenticate the user freshly, but IsPassive requests that the identity provider not do this.

Action:
Change one of the values to false.

BEA-096623
Item has already expired on {0}, it will not be cached.

Category:
Security

Cause:
The configured timeout may be too short.

Action:
Check the timeout configuration.

BEA-096624
The "{1}" parameter passed to "{0}" must not be null.

Category:
Security

Cause:
A null "{1}" parameter was passed to "{0}".

Action:
Ensure that a valid reference is passed.

BEA-096625
The parameter MaxCacheSize or timeout must not be a negative number.

Category:
Security

Cause:
The parameter MaxCacheSize or timeout cannot be a negative number.

Action:
Change the MaxCacheSize parameter or timeout to zero or a positive number.

BEA-096626
The partner name cannot be changed at partner update operation.

Category:
Security

Cause:
The user tried to change the read-only partner name.

Action:
Set the partner name back to the original name.

BEA-096627
There is no login URL configured in Identity Provider Site.

Category:
Security

Cause:
No login URL was configured in the Identity Provider Site.

Action:
Configure a valid login URL in SingleSignOnServicesMBean.

BEA-096628
The value configured for NameMapper attribute: {0} is not valid.

Category:
Security

Cause:
The name mapper class {0} is not in the classpath or it does not implement a name mapper interface.

Action:
Ensure that the name mapper class {0} is in the classpath and implements a name mapper interface.

BEA-096629
The confirmation method passed through Context handler: {0} is not valid.

Category:
Security

Cause:
An invalid confirmation method was passed through the Context handler.

Action:
Make sure the confirmation method passed through Context handler {0} has a valid value.

BEA-096630
Using expired certificate at alias {0} for signing.

Category:
Security

Cause:
An attempt was made to use an expired certificate at alias {0} for signing, but allow expired cert is false.

Action:
Use a valid certificate for signing.

BEA-096631
Using not yet valid certificate at alias {0} for signing.

Category:
Security

Cause:
A not yet valid certificate was used at alias {0} for signing, but allow expired cert is false.

Action:
Use a valid certificate for signing.

BEA-096632
Binding type {0} is unsupported, endpoint with this binding is filtered out from partner.

Category:
Security

Cause:
The binding type that was used is not supported.

Action:
Use a binding type that is supported.

BEA-096633
The partner metadata file does not contain an XML root element of <EntityDescriptor>.

Category:
Security

Cause:
The partner metadata file content is not supported.

Action:
Update the partner metadata content or obtain a new partner metadata file.

BEA-096634
Cannot get the single sign-on sign certificate to sign the {0} in the key store.

Category:
Security

Cause:
Either no single sign-on sign certificate is defined in the local configuration or the key/keystore is invalid.

Action:
Correct the key configuration for SAML services.

BEA-096635
Error occurs when encrypting {0}.

Category:
Security

Cause:
Error occurs when encrypting {0}.

Action:
Check debug log for specific encryption error on {0}.

BEA-097000
Service info was not found for service to shut it down, {0}

Category:
Engine

Cause:
Service info was not found when shutting down a service.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097001
Configuration problems detected.

Category:
Engine

Cause:
A bad configuration was supplied.

Action:
Check and fix the configuration.

BEA-097002
Configuration canno be modified after the engine has been started.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine configuration was modified after the engine was started.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097004
Engine has already been started.

Category:
Engine

Cause:
An attempt was made to start the engine after it had been started.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097005
Unable to find ServiceConfig.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine cannot be configured.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097006
Duplicate service name {0}.

Category:
Engine

Cause:
The service engine was configured with a duplicate service name.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097007
Logger not found.

Category:
Engine

Cause:
The service engine could not find the logger.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097008
An attempt was made to access the ServiceEngine after it had already been shut down.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine was accessed after being shut down.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097009
Engine already shut down.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine has already been shut down.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097010
Service {0} not found.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine cannot find the service.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097011
Service {0} not exposed.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine looked up a service that it cannot expose.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097012
Service {0} does not implement ServiceLifecycleSpi.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine was configured with a service that it cannot use.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097013
Null service {0} loaded.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine was configured with a null service.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097014
Classloader not found for service {0}.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine was configured with a service but the service's classloader could not be found.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097015
Failure loading service {0} using class {1}.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine could not load a service.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097016
Service {0} is dependent upon {1} which does not exist.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine could not find a dependent service.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097017
Service name not specified.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine could not find a service.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097018
Attempt to remove lifecycle impl for {0} when {1} dependencies still exist.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine attempted to remove a service that still has dependencies.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097019
Attempt to remove dependencies for {0} when no dependencies still exist.

Category:
Engine

Cause:
This is an internal WebLogic Server error indicating that the service engine attempted to remove dependencies for a service when no dependencies exist.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097020
Internal consistency failure in {0}

Category:
Engine

Cause:
This is an internal WebLogic Server error.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097021
Manageable Service {0} not found.

Category:
Engine

Cause:
This is an internal WebLogic Server error. An attempt was made to look up a manageable service but it was not found.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097022
Service {0} is not manageable.

Category:
Engine

Cause:
This is an internal WebLogic Server Error. An attempt was made to look up a manageable service and a service with the requested name was found, but it was not a manageable service.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097500
{0} requires a {1} to be supplied for configuration but it was not supplied.

Category:
Security

Cause:
The configuration supplied to {0} was incorrect.

Action:
Ensure that the configuration supplied for {0} is correct.

BEA-097501
{1} supplied to {0} is missing {2}

Category:
Security

Cause:
The configuration supplied to {0} was incorrect.

Action:
Ensure that the configuration supplied for {0} is correct.

BEA-097502
MaxIdentitiesInCache value for the IdentityCacheService is invalid {0}

Category:
Security

Cause:
The value supplied for MaxIdentitiesInCache for the IdentityCacheService was invalid.

Action:
Change MaxIdentitiesInCache to a valid value.

BEA-097503
The configured CertPathBuilder service returned a non X.509 certificate path.

Category:
Security

Cause:
The CertPathBuilder was configured with an incorrect certificate path for an X.509 certificate.

Action:
Correct the configured CertPathBuilder service.

BEA-097504
AdjudicationService does not have an AdjudicatorV2Name but has multiple AccessDecision providers.

Category:
Security

Cause:
The AdjudicationService has multiple AccessDecision providers, but there are no providers that implement the AdjudicatorV2 interface.

Action:
Configure an adjudicator that implements the AdjudicatorV2 interface.

BEA-097505
None of the configured {0} support JAAS login.

Category:
Security

Cause:
There are no authentication providers configured to support JAAS login.

Action:
Configure at least one authentication provider that supports JAAS login.

BEA-097506
An AuthorizationProvider returned a null AccessDecision.

Category:
Security

Cause:
An AuthorizatonProvider was not able to return an AccessDecision.

Action:
Examine the AuthorizationProvider.

BEA-097507
{0} may only be called if hasChallengeIdentityCompleted returns false.

Category:
Security

Cause:
This is an internal WebLogic Server error.

Action:
Contact My Oracle Support.

BEA-097508
{0} may only be called if hasChallengeIdentityCompleted returns true.

Category:
Security

Cause:
This is an internal WebLogic Server error.

Action:
Contact My Oracle Support.

BEA-097509
{0} returned a null {1}.

Category:
Security

Cause:
There is a configuration problem because a null object was returned.

Action:
Examine the specific objects referenced in the error message to see what may be the cause.

BEA-097510
Got back a null {0} object.

Category:
Security

Cause:
There is a configuration problem because a null object was returned.

Action:
Examine the specific object referenced in the error message to see what may be the cause.

BEA-097511
Expected a {0} object but did not get one.

Category:
Security

Cause:
There is a configuration problem because an object was expected and a different object was returned.

Action:
Check the configuration.

BEA-097512
Multiple challenges not supported.

Category:
Security

Cause:
An attempt has made to handle multiple challenges with a provider that does not support it.

Action:
Correct the code or configure a ChallengeIdentityAsserter that supports multiple challenges.

BEA-097513
Incorrect Cert Path type, expecting a {0} type.

Category:
Security

Cause:
The wrong type of Cert Path was passed due to incorrect configuration.

Action:
Correct the configured CertPathBuilder service.

BEA-097514
Multiple {0} support the token type {1}.

Category:
Security

Cause:
The configuration is not correct.

Action:
Remove one of the objects supporting this token token type from the configuration.

BEA-097515
Unsupported token type {0}

Category:
Security

Cause:
No objects are configured to support the specified token type.

Action:
Configure an object that supports this token type.

BEA-097516
Unable to validate a non X.509 certificate path.

Category:
Security

Cause:
Not all certificate paths are of type X.509.

Action:
Correct the configured CertPathBuilder service to ensure that all certificate paths are of type X.509.

BEA-097517
A certificate is self signed but it is not the last certificate in the chain, see {0}

Category:
Security

Cause:
There is a certificate chain but one of the certificates is self signed.

Action:
Ensure that the certificate chain is correct.

BEA-097518
Issue DN mismatch error. Issued: {0} does not match issuer: {1}.

Category:
Security

Cause:
There is an inconsistent certificate chain. The issuer DN of a certificate did not match the subject DN of the next certificate in the chain.

Action:
Ensure that the the certificates in the chain correctly refer to each other.

BEA-097519
Certificate not signed by issuer. Certificate: {0} not signed by issuer: {1}.

Category:
Security

Cause:
There is an inconsistent certificate chain. A certificate was not signed by the next certificate in the chain.

Action:
Ensure that the the certificates in the chain correctly refer to each other.

BEA-097520
Capacity {0} greater than maximum {1}

Category:
Security

Cause:
The specified queue capacity is too large.

Action:
Reduce the specified queue capacity.

BEA-097521
Maximum capacity {0} is greater than the allowed {1}

Category:
Security

Cause:
The specified maximum queue capacity is larger than allowed.

Action:
Reduce the specified maximum capacity.

BEA-097522
Initial specified capacity of {0} is illegal.

Category:
Security

Cause:
The specified capacity is illegal.

Action:
Specify a correct capacity.

BEA-097523
Illegal load factor.

Category:
Security

Cause:
An illegal load factor was specified.

Action:
Specify a load factor greater than 0 and less than 1.

BEA-097524
No appropriate registered configuration to handle the AppConfigurationEntry named: {0}

Category:
Security

Cause:
No appropriate JAASConfiguration has been registered.

Action:
Register the appropriate JAASConfiguration

BEA-097525
Null JAASConfiguration.

Category:
Security

Cause:
An attempt was made to register a null JAASConfiguration.

Action:
Register a non-null JAASConfiguration.

BEA-097526
Duplicate JAASConfiguration.

Category:
Security

Cause:
An attempt was made to register a JAASConfiguration twice.

Action:
Do not attempt to register the JAASConfiguration twice.

BEA-097527
JAASConfiguration not registered.

Category:
Security

Cause:
An attempt was made to unregister a JAASConfiguration that is not registered.

Action:
Do not attempt to unregister an unregistered JAASConfiguration.

BEA-097528
A null {0} was specified.

Category:
Security

Cause:
This method cannot accept a null argument.

Action:
Do not pass in a null argument.

BEA-097529
The principal validators {0} and {1} both validate the same principal types.

Category:
Security

Cause:
There can only be one principal validator for each principal type.

Action:
Correct the configuration.

BEA-097530
No {1} found in method {0}

Category:
Security

Cause:
Objects should have been configured but were not.

Action:
Correct the configuration.

BEA-097531
Method {0} was unable to sign a principal.

Category:
Security

Cause:
Something was wrong with the principal or the principal validator was incorrect.

Action:
Correct the configuration.

BEA-097532
Null parameter supplied to method {0}.

Category:
Security

Cause:
A parameter was not correctly specified. This is most likely a coding error.

Action:
Check the code for an incorrectly specified parameter.

BEA-097533
SecurityProvider service class name for {0} is not specified.

Category:
Security

Cause:
The SecurityProviderConfig does not contain a SecurityProvider service class name.

Action:
Examine the specific objects referenced in the error message to see what may be the cause, and take appropriate action.

BEA-097534
Failed to obtain an instance of class {0}.

Category:
Security

Cause:
There is a possible configuration problem. A {0} class name is invalid, or is not in the class path. It does not have a public no argument constructor, or has the constructor which failed to execute.

Action:
Check the configuration.

BEA-097535
The configuration does not define a store, but providers that require a store are in use.

Category:
Security

Cause:
There is no store servoce defined in the configuration.

Action:
Configure a store service.

BEA-097536
The {0} service can not be found for {1}.

Category:
Security

Cause:
A null was returned when doing a service lookup.

Action:
Check the configuration to see if the missing service was actually configured.

BEA-097537
The {2} setting supplied in the {1} configuration to {0} is invalid.

Category:
Security

Cause:
The configuration setting {2} supplied in {1} to {0} is incorrect.

Action:
Ensure that the configuration supplied for {0} is correct.

BEA-097538
The keystore {0} of type {1} could not be accessed.

Category:
Security

Cause:
The keystore {0} of type {1} could not be accessed and the configuration may be incorrect.

Action:
Ensure that the keystore {0} of type {1} can be accessed.

BEA-097539
Connection to the database is currently unavailable.

Category:
Security

Cause:
The database configuration may be incorrect or the database was not available.

Action:
Ensure that the database configuration is correct and that the database is available.

BEA-097540
Property could not be parsed and will be skipped. Format must be name=value. Format found: {0}

Category:
Security

Cause:
The properties configured for the database pool could not be parsed and will be skipped.

Action:
Check the format of the properties supplied to the configuration

BEA-097541
{0} requires a {1}, this was not available.

Category:
Security

Cause:
This may be a coding error or a configuration error.

Action:
Check for configuration errors. If the configuration appears valid, contact My Oracle Support.

BEA-097542
Connection was not found by name {0}.

Category:
Security

Cause:
The named SQL connection was not found.

Action:
Check the log to see whether there is a connection pool checkout failure and determine the cause.

BEA-097543
Store service properties must not be null.

Category:
Security

Cause:
This may be a store service configuration error.

Action:
Check the store service configuration.

BEA-097544
Get a null {0} value in store service properties.

Category:
Security

Cause:
A data store connection was not specified in the store service properties.

Action:
Check the store service configuration.

BEA-097545
The internal state of the token is not consistent, possibly due to a failure during encoding/decoding the token.

Category:
Security

Cause:
This is an internal WebLogic Server error.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097546
Timestamp is not of the correct length: {0}.

Category:
Security

Cause:
The timestamp format was not correct.

Action:
Fix the timestamp format.

BEA-097547
Timestamp contains illegal non-digit characters: {0}.

Category:
Security

Cause:
The timestamp format is not correct.

Action:
Fix the timestamp format.

BEA-097548
Timestamp has invalid timezone designator: {0}.

Category:
Security

Cause:
The timestamp format is not correct.

Action:
Fix the timestamp format.

BEA-097549
Timestamp is missing timezone designator: {0}.

Category:
Security

Cause:
The timestamp format is not correct.

Action:
Fix the timestamp format.

BEA-097550
Month value is out-of-range for given year: {0}.

Category:
Security

Cause:
The timestamp format is not correct.

Action:
Fix the timestamp format.

BEA-097551
Day of month value is out-of-range for given month and year: {0}.

Category:
Security

Cause:
The timestamp format is not correct.

Action:
Fix the timestamp format.

BEA-097552
SPNEGO token trying to be constructed with invalid parsed information.

Category:
Security

Cause:
The parsed information is invalid.

Action:
This is likely an internal WebLogic Server error. If this occurs again, contact My Oracle Support.

BEA-097553
SAMLSourceSite: Error while generating {0}: {1}.

Category:
Security

Cause:
{0} Could not be generated.

Action:
This is likely an internal WebLogic Server error. If this occurs again, contact My Oracle Support.

BEA-097554
Queries that test at least one scope primary key must test all primary keys with a lower index.

Category:
Security

Cause:
Not all primary keys with a lower index were tested.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097555
This store does not support nested containers (that is, collections of collections).

Category:
Security

Cause:
You are using nested containers for a store that does not support them.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-097556
Primary key field must not be null: {0}.

Category:
Security

Cause:
There was no value found for the primary key.

Action:
Check the query to see if the primary key is not null or empty.

BEA-097558
FederationServicesMBean configuration Protocol Signing Key {0} is invalid.

Category:
Security

Cause:
The FederationServicesMBean Protocol Signing Key was configured with an invalid value.

Action:
Check the key information to see if it is valid.

BEA-097559
FederationServicesMBean configuration SSL Client Key {0} is invalid.

Category:
Security

Cause:
The FederationServicesMBean SSL Client Key was configured with an invalid value.

Action:
Check the key information to see if it is valid.

BEA-097560
Invalid Source Site configuration, {0} must not be null or empty.

Category:
Security

Cause:
The Source Site configuration is missing.

Action:
Check the configuration to see if there is a null or empty field.

BEA-097561
Store service is not initialized properly.

Category:
Security

Cause:
The store service was configured incorrectly.

Action:
Check the Store service configuration.

BEA-097562
Cannot forward to custom post form, please check if the post form configuration is valid.

Category:
Security

Cause:
The post form configuration was invalid.

Action:
Fix the post form configuration.

BEA-097563
Connection was not found by name {0}.

Category:
Security

Cause:
There was a configuration error or an internal WebLogic Server error.

Action:
Ensure that the specified data source is configured. In addition, check the log to see whether there is a connection pool checkout failure and find the cause.

BEA-097564
The JDBC Connection Service initialization failed.

Category:
Security

Cause:
The configuration is incorrect.

Action:
Check that the SQL configuration has been specified properly.

BEA-098500
Decimal is too short.

Category:
Security

Cause:
The value length is less than or equal to 0.

Action:
Pass in a correct value.

BEA-098501
Decimal contains incorrect characters.

Category:
Security

Cause:
The specified decimal value contains incorrect characters.

Action:
Pass in a correct value.

BEA-098502
Hex binary data bad length.

Category:
Security

Cause:
The length of hex binary data is uneven.

Action:
Pass in a correct value.

BEA-098503
Invalid hex digit.

Category:
Security

Cause:
An invalid hexadecimal digit was encountered.

Action:
Pass in a correct value.

BEA-098504
Invalid RFC822 name: {0}

Category:
Security

Cause:
An invalid RFC822 name attribute value was passed.

Action:
Pass in a valid RFC822 name attribute value.

BEA-098505
Illegal X500 value: {0}

Category:
Security

Cause:
An illegal X500 value was passed.

Action:
Pass in a valid X500 name attribute value.

BEA-098506
Not enough BASE64 bytes

Category:
Security

Cause:
The atom cannot be decoded because not enough bytes were available.

Action:
Correct the BASE64 value.

BEA-098507
Incorrect XPathVersion

Category:
Security

Cause:
An unsupported XPathVersion was specified.

Action:
Use a supported XPathVersion

BEA-098508
Negative month with non-zero year

Category:
Security

Cause:
The month cannot be negative if the year is a non-zero value.

Action:
Correct the month or year value.

BEA-098509
Month and year are zero.

Category:
Security

Cause:
Both the month and the year are zero. At least one of the month and year must be non-zero.

Action:
Correct the month or year value.

BEA-098510
Method {0} had an internal WebLogic Server error.

Category:
Security

Cause:
This is an internal WebLogic Server error

Action:
Contact My Oracle Support and provide them with the log files.

BEA-098511
Illegal explicit to non-explicit time zone comparison

Category:
Security

Cause:
It is illegal to compare time values when one has an explicit time zone and the other does not.

Action:
Correct the time-zone specification mismatch.

BEA-098512
Could not schedule Audit log rotate trigger

Category:
Security

Cause:
There is an issue with the parameters configured on the Audit provider.

Action:
Correct the parameters configured on the Audit provider.

BEA-098513
Service Initialization when getting service with {0} service name.

Category:
Security

Cause:
The service with {0} service name was not correctly initialized in the service engine.

Action:
Correctly initialize the service in the service engine.

BEA-098514
Failed to generate a certificate thumbprint: {0}.

Category:
Security

Cause:
The thumbprint algorithm cannot be found or a certificate encoding error occurred.

Action:
Examine the error message to determine the exact cause and take appropriate action.

BEA-098515
{1} cannot be {2}.

Category:
Security

Cause:
This is most likely a coding error.

Action:
Pass a valid {1} to the method {0}.

BEA-098516
The CertificateRegistry could not build a certificate path for the thumbprint {0}. This indicates that either someone is trying to access the server with an untrusted thumbprint or that the administrator has forgotten to register a certificate with this thumbprint in the CertificateRegistry.

Category:
Security

Cause:
The CertificateRegistry does not contain a certificate whose thumbprint is {0}.

Action:
If you want to trust the thumbprint {0}, then register a certificate with this thumbprint in the CertificateRegistry.

BEA-098517
Failed to get SAML assertion info: {0}.

Category:
Security

Cause:
A SAML assertion document parsing error occurred.

Action:
Examine the error message to determine the cause and take appropriate action.

BEA-098518
The environment does not support anonymous, please log in.

Category:
Security

Cause:
The method getAnonymousIdentity of IdentityService returned null.

Action:
Check the environment configuration.

BEA-098519
Invalid file store password or the file has been invalidly changed.

Category:
Security

Cause:
The password for the file store is illegal or the file is modified.

Action:
Ensure that the store password is not changed and the file is not modified either.

BEA-098520
Unable to instantiate the CSSDelegate implementation.

Category:
Security

Cause:
The CSS Delegate implementation is not in the classpath.

Action:
Check the CSS classpath.

BEA-098521
Invalid principal class name {0} is entered to the PrincipalFactory create() API.

Category:
Security

Cause:
An invalid principal class name was entered to the PrincipalFactory create() API.

Action:
Ensure that the principal class derives from WLSPrincipal.

BEA-098522
Unable to instantiate the principal instance for principal class {0}.

Category:
Security

Cause:
The principal class {0} is not in the classpath.

Action:
Ensure that the class {0} is in the classpath.

BEA-098523
Unable to instantiate the PrincipalConfigurationDelegate instance.

Category:
Security

Cause:
The related class, either WLSPrincipalConfigurationDelegateImpl or OPPrincipalConfigurationDelegateImpl, is not in the classpath.

Action:
Ensure that WLSPrincipalConfigurationDelegateImpl and OPPrincipalConfigurationDelegateImpl are in the classpath.

BEA-099000
Null {0} parameter supplied to method {1}.

Category:
Security

Cause:
A parameter was not correctly specified. This is most likely a coding error.

Action:
Check for a coding error.

BEA-099001
Invalid ContextHandler value for {0} type: expect to {1} type.

Category:
Security

Cause:
This most likely was caused by an environment error.

Action:
Check and update the indicated context element.

BEA-099002
Null or empty certificate chain

Category:
Security

Cause:
This was most likely caused by an environment error.

Action:
Check and update the indicated context element.

BEA-099003
SAMLBeanUpdateListener {0}: {1} failed with exception: {2}

Category:
Security

Cause:
This was most likely caused by an environment error.

Action:
Check and update the environment.

BEA-099004
SAMLCreateAssertion: Exception while creating authentication statement.: {0}

Category:
Security

Cause:
This was most likely caused by an environment error.

Action:
Check and update the environment.

BEA-099005
SAMLCreateAssertion: can't map confirmation method

Category:
Security

Cause:
This was most likely caused by an environment error.

Action:
Check and update the environment.

BEA-099006
provider {0}: SAML Key Manage failed to validate key (Assertions signing) configuration in the FederationServicesMBean, key alias: {1}

Category:
Security

Cause:
This was most likely caused by an environment error.

Action:
Check and update the environment.

BEA-099007
Provider {0} not initialized: method {1} could not be called.

Category:
Security

Cause:
An internal WebLogic Server error occurred when the SAML provider was initialized.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-099008
Store service properties must not be null.

Category:
Security

Cause:
This was most likely caused by a configuration error.

Action:
Check the Store service configuration.

BEA-099009
Get a null {0} value in store service properties.

Category:
Security

Cause:
This was most likely caused by a configuration error.

Action:
Check the Store service configuration.

BEA-099010
Unable to derive key.

Category:
Security

Cause:
The input {0} is null or empty.

Action:
Verify that the input parameter {0} is not null or empty.

BEA-099011
Unable to get digest value for a password.

Category:
Security

Cause:
The input {0} is null or empty.

Action:
Verify that the input parameter {0} is not null or empty.

BEA-099012
Unable to create password digest - UTF-8 encoding required but unavailable:{0}.

Category:
Security

Cause:
An internal WebLogic Server error occurred while performing a message digest.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-099013
Invalid token type {0} received by the LDAP X509 certificate identity asserter.

Category:
Security

Cause:
This was likely caused by the provider not being properly configured.

Action:
Check the provider configuration.

BEA-099014
{0}: {1} is null

Category:
Security

Cause:
A parameter was not correctly specified.

Action:
Check for a coding error.

BEA-099015
The format for import or export is invalid.

Category:
Security

Cause:
The format for import or export was invalid.

Action:
Check the string used for import or export.

BEA-099016
Could not get partner by partner id: {0}.

Category:
Security

Cause:
The partner could not be retrieved using the partner id: {0}.

Action:
Check the registry to see if the partner exists.

BEA-099017
Could not add partner with null partner id.

Category:
Security

Cause:
The partner id is null.

Action:
Check the partner information.

BEA-099018
Update business object failed, could not determine the object to update.

Category:
Security

Cause:
The object for updating could not be found.

Action:
Check the registry to find the correct partner for updating.

BEA-099019
Could not parse assertion: {0}.

Category:
Security

Cause:
An assertion was received that could not be properly parsed.

Action:
Check the SAML assertion or contact My Oracle Support.

BEA-099020
Assertion validity check failed: {0}.

Category:
Security

Cause:
An assertion was received that did not pass validation.

Action:
Check the SAML assertion or contact My Oracle Support.

BEA-099021
Signature required but assertion is not signed.

Category:
Security

Cause:
The assertion is not signed.

Action:
Check the SAML assertion.

BEA-099022
Signature is required but no signing certificate alias configured.

Category:
Security

Cause:
No signing certificate alias is configured.

Action:
Check the SAML configuration.

BEA-099023
Unable to find trusted certificate for alias: {0}.

Category:
Security

Cause:
The trusted certificate was not available from the certificate registry.

Action:
Check the SAML configuration.

BEA-099024
Signature verified but no certificate found to check trust.

Category:
Security

Cause:
No certificate was found to check the trust.

Action:
Check the signature for the certificate.

BEA-099025
Certificate in signature does not match configured signing cert.

Category:
Security

Cause:
The certificate in the signature does not match the configured signing cert.

Action:
Check the certificate information in the partner registry.

BEA-099026
Certificate is not trusted.

Category:
Security

Cause:
An assertion was received for which the signing certificate is not trusted.

Action:
Check the SAML configuration and add the certificate to the registry.

BEA-099027
Could not create name mapper: {0}.

Category:
Security

Cause:
An error occurred while creating an instance of the configured SAML name mapper.

Action:
Check the details of the error message to determine the proper handling.

BEA-099028
Mapping name error: {0}.

Category:
Security

Cause:
An error occurred while invoking an instance of the configured SAML name mapper.

Action:
Check the details of the error message to determine the proper handling.

BEA-099029
Mapping group error: {0}.

Category:
Security

Cause:
An error occurred while invoking an instance of the configured SAML name mapper.

Action:
Check the details of the error message to determine the proper handling.

BEA-099030
NameMapper returned no username mapping.

Category:
Security

Cause:
An instance of the configured SAML name mapper returned no user or group information.

Action:
Check the SAML assertion or contact My Oracle Support.

BEA-099031
Assertion is invalid before {0}.

Category:
Security

Cause:
The received SAML assertion is not yet valid.

Action:
Check the SAML configuration, the system clock or contact the SAML Identity Provider.

BEA-099032
Assertion is invalid on or after {0}.

Category:
Security

Cause:
The received SAML assertion has expired.

Action:
Check the SAML configuration, the system clock or contact the SAML Identity Provider.

BEA-099033
No matching audience.

Category:
Security

Cause:
The received SAML assertion audience conditions was not satisfied.

Action:
Check the SAML configuration or contact the SAML Identity Provider.

BEA-099034
Unrecognized assertion condition (schema extension).

Category:
Security

Cause:
The received SAML assertion contained an unknown condition.

Action:
Contact the SAML Identity Provider for information on how to correct the problem.

BEA-099035
No target in context handler.

Category:
Security

Cause:
An internal WebLogic Server error occurred while determining the SAML target.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-099036
Could not map Confirmation Method URN: {0}.

Category:
Security

Cause:
The received SAML assertion contained an unknown confirmation method.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-099037
Could not find asserting party matching assertion and context.

Category:
Security

Cause:
The SAML partner could not be determined from the received SAML assertion.

Action:
Check the SAML assertion or contact My Oracle Support.

BEA-099038
Could not verify signature: {0}.

Category:
Security

Cause:
The signature from the received SAML assertion could not be verified.

Action:
Check the SAML assertion or contact My Oracle Support.

BEA-099039
No issuer URI configured for asserting party.

Category:
Security

Cause:
The SAML asserting party was not configured with an issuer URI.

Action:
Check the SAML configuration.

BEA-099040
Assertion issuer does not match issuer configured for asserting party.

Category:
Security

Cause:
The issuer from the received SAML assertion could not be verified.

Action:
Check the SAML assertion against the SAML configuration.

BEA-099041
Assertion subject confirmation method does not match asserting party configuration.

Category:
Security

Cause:
The subject confirmation from the received SAML assertion could not be verified.

Action:
Check the SAML assertion against the SAML configuration.

BEA-099046
Illegal value for {0}: {1}.

Category:
Security

Cause:
This error has multiple possible causes. When using the PasswordHashUtility, an invalid command line argument was passed. For SAML, it means that there is an invalid SAML provider configuration.

Action:
Check the command line argument for the parameter specified in the message or check the SAML provider configuration.

BEA-099047
Missing parameter {0}.

Category:
Security

Cause:
The SAML provider configuration is invalid.

Action:
Check the SAML provider configuration.

BEA-099048
Invalid {0} value {1} for {2}.

Category:
Security

Cause:
An invalid configuration was supplied for the SAML provider.

Action:
Check the SAML provider configuration based on the configuration parameter from the error message.

BEA-099049
Could not load SAML partner registry schema file {0}.

Category:
Security

Cause:
An internal WebLogic Server error occurred while loading the SAML partner registry.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-099050
Could not generate XML Schema from SAML partner registry schema file: {0}.

Category:
Security

Cause:
An internal WebLogic Server error occurred while loading the SAML partner registry.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-099051
ImportMode = fail, partnerID {0} exists, import operation terminated.

Category:
Security

Cause:
The SAML partner could not be imported because the partner entry already exists.

Action:
Check the SAML configuration or select a different SAML partner import mode.

BEA-099052
Could not locate {0} {1} in the import XML document, import operation abort.

Category:
Security

Cause:
The SAML partner could not be imported because the partner or certificate could not be found.

Action:
Check the SAML partner registry file based on the information from the error message.

BEA-099053
{0} {1} already exists, Import operation fail.

Category:
Security

Cause:
The SAML partner could not be imported because the partner or certificate already exists.

Action:
Check the SAML configuration based on the information from the error message.

BEA-099054
Error getting {0} {1} from registry, Import operation fail.

Category:
Security

Cause:
The SAML partner could not be imported because the partner or certificate could not be located.

Action:
Check the SAML configuration based on the information from the error message.

BEA-099055
Could locate {0} {1} from registry.

Category:
Security

Cause:
The SAML partner could not be imported because the partner or certificate could not be located.

Action:
Check the SAML configuration based on the information from the error message.

BEA-099056
Could not export partner registry data ldift: {0}.

Category:
Security

Cause:
An internal WebLogic Server error occurred while exporting a SAML partner.

Action:
Contact My Oracle Support and provide them with the log files.

BEA-099057
Could not decrypt password: {0}.

Category:
Security

Cause:
The supplied password could not be read.

Action:
Check that the password value is correct or contact My Oracle Support.

BEA-099058
No sender certificate is provided for checking trust.

Category:
Security

Cause:
The received SAML assertion could not be trusted because no certificate was provided.

Action:
Check the SAML configuration, the SSL configuration or contact My Oracle Support.

BEA-099059
There is no {0} in {1}.

Category:
Security

Cause:
The received SAML assertion could not be validated.

Action:
Check the details of the error message to determine the proper handling.

BEA-099060
The URL specified for the data store connection is invalid: {0},please check all host configuration parameters.

Category:
Security

Cause:
This was most likely caused by a configuration error.

Action:
Check all host configuration.

BEA-099061
Hash algorithm {0} was not found

Category:
Security

Cause:
The JCE configuration is most likely not set up to support the algorithm.

Action:
Review the JCE configuration to ensure the hash algorithm is available for use.

BEA-099062
The {0} password hash algorithm is not usable.

Category:
Security

Cause:
The password algorithm name was not found to be supported by the JCE crypto configuration.

Action:
Verify that the password algorithm is specified correctly, and that the JCE configuration supports the algorithm.

BEA-099063
Plaintext password usage was rejected.

Category:
Security

Cause:
Plaintext passwords are configured to not be allowed, but a Plaintext password was either found or was attempted to be saved.

Action:
If the failure occurred during authentication, review the plaintext passwords and correct them. If the failure occurred while changing a password, review the password style settings to ensure that they specify a non-plaintext style.

BEA-099064
Plaintext password is not allowed and unable to parse the stored hashed password.

Category:
Security

Cause:
Plaintext passwords are configured to not be allowed, but the hashed password could not be parsed.

Action:
If the failure occurred during authentication, review the plaintext passwords and correct them. If the failure occurred while changing a password, review the password style settings to ensure that they specify a non-plaintext style.

BEA-099065
Password ("quit" to end)

Category:
Security

Cause:
The password hash utility internally uses this prompt for a password.

Action:
This is the prompt that will be used by the password hash utility.

BEA-099066
Usage: Java com.bea.security.utils.authentication.PasswordHashUtility [-a algorithm] [-s size] password* "algorithm" is the name of the hash algorithm "size" is the length of the salt characters "passwords" are the plain text passwords to be hashed. None for interactive mode.

Category:
Security

Cause:
The is the text the password hash utility displays for usage of the utility.

Action:
This is the usage text that will be used by the password hash utility.

BEA-099067
The minimum length of password must not be greater than the maximum length of password.

Category:
Security

Cause:
System password validation was configured with an invalid password length.

Action:
Change the value for minimum or maximum length of a password.

BEA-099068
The user name cannot be empty.

Category:
Security

Cause:
The user name is null.

Action:
Input correct user name information.

BEA-099069
The password length cannot be less than {0}.

Category:
Security

Cause:
The current password length is less than {0}.

Action:
Change your password, and try again.

BEA-099070
The password length cannot be greater than {0}.

Category:
Security

Cause:
The current password length is greater than {0}.

Action:
Change your password, and try again.

BEA-099071
The password cannot contain or be equal to your username.

Category:
Security

Cause:
The password contains or is the same as your username.

Action:
Change your password, and try again.

BEA-099072
The password cannot contain or be equal to the reverse of your username.

Category:
Security

Cause:
The password contains or is equal to the reverse of your username.

Action:
Change your password, and try again.

BEA-099073
The maximum instances of a character in a password cannot be greater than {0}.

Category:
Security

Cause:
The maximum occurrences of a character in the password is greater than what is allowed by the configuration of system password validation.

Action:
Change your password, and try again.

BEA-099074
The maximum repeating consecutive characters in a password cannot be greater than {0}.

Category:
Security

Cause:
The repetition of a character in the password is greater than what is allowed by the configuration of system password validation.

Action:
Reduce the repeating consecutive characters in your password, and try again.

BEA-099075
The number of alphabetic characters in a password cannot be less than {0}.

Category:
Security

Cause:
The number of alphabetic characters in the password is less than what is required by the configuration of system password validation.

Action:
Add more alphabetic characters in your password.

BEA-099076
The number of numeric characters in a password cannot be less than {0}.

Category:
Security

Cause:
The number of numeric characters in the password is less than {0}.

Action:
Add more numeric characters in your password.

BEA-099077
The number of lowercase characters in a password cannot be less than {0}.

Category:
Security

Cause:
The number of lowercase characters in the password is less than {0}.

Action:
Add more lowercase characters in your password.

BEA-099078
The number of uppercase characters in a password cannot be less than {0}.

Category:
Security

Cause:
The number of uppercase characters in the password is less than {0}.

Action:
Add more uppercase characters in your password.

BEA-099079
The number of non-alphanumeric characters in a password cannot be less than {0}.

Category:
Security

Cause:
The number of non-alphanumeric characters in the password is less than {0}.

Action:
Add more non-alphanumeric characters in your password.

BEA-099080
The user password cannot be null.

Category:
Security

Cause:
The user password is null.

Action:
Input your password, and try again.

BEA-099081
Illegal command line.

Category:
Security

Cause:
Command line syntax is not correct.

Action:
Retype the command line and try again.

BEA-099082
Could not configure attribute {0} in MBean {1}.

Category:
Security

Cause:
The method to configure this attribute could not be found or the parameter for this method could not be created.

Action:
Refer to the MBean javadoc to verify whether the MBean attribute name is correct.

BEA-099083
The key {0} in property file is in the wrong format.

Category:
Security

Cause:
The key {0} in property file is in the wrong format.

Action:
Modify the property file and use a valid format for the key.

BEA-099084
Could not create MBean.

Category:
Security

Cause:
The MBean type or MBean class in property file may not be correct.

Action:
Check the MBean type or MBean class in the property file.

BEA-099085
Unknown MBeanResource ActionType {0}.

Category:
Security

Cause:
The MBean resource method that a caller is attempting to access is unknown.

Action:
Modify your entitlement policy and try again.

BEA-099086
Get null or empty encrypted value. An encrypted value must not be null or empty.

Category:
Security

Cause:
The encrypted value is null or empty.

Action:
Check the encrypted value.

BEA-099087
The MaxPasswordLength must not be less than MinAlphabeticCharacters+MinNumericCharacters+MinNonAlphanumericCharacters.

Category:
Security

Cause:
System password validation was configured with an invalid password length.

Action:
Change the system password validation configuration lengths.

BEA-099088
The MaxPasswordLength must not be less than MinLowercaseCharacters+MinUppercaseCharacters+MinNumericCharacters+MinNonAlphanumericCharacters.

Category:
Security

Cause:
System password validation was configured with an invalid password length.

Action:
Change the system password validation configuration lengths.

BEA-099089
The NegotiateCredentialMapper could not get credentials. The requestor is {0}. The initiator is {1}. The resource is {2}. The exception is {3}.

Category:
Security

Cause:
An unexpected exception occurred when trying to get the credentials.

Action:
Read the exception text from the log message for more information on diagnosing the problem.

BEA-099090
The NegotiateCredentialMapper could not get credentials for initiator with String type. The requestor is {0}. The initiator is {1}. The resource is {2}.

Category:
Security

Cause:
The initiator should not be a String while acquiring credentials with NegotiateCredentialMapperProvider.

Action:
Try the getCredentials() method with a Subject as the initiator.

BEA-099091
Illegal parameter type.

Category:
Security

Cause:
An initiator with String type is not supported by NegotaiteCredentialMapper for method getCredential().

Action:
Try the method getCredentials() with Subject as the initiator type.

BEA-099092
Trust group {0} not found.

Category:
Security

Cause:
The group could not be found as the group parameter that was passed to the method is not registered in the security provider.

Action:
Pass in a trust group that exists.

BEA-099093
The security provider already has a trust group registered with {0}.

Category:
Security

Cause:
The trust group {0} already exists in the security provider.

Action:
Pass in another trust group name.

BEA-099094
The trust group is null or empty.

Category:
Security

Cause:
An empty or null trust group was passed but this is not supported.

Action:
Modify the code to pass a non-null and non-empty trust group.

BEA-099095
The trust group wildcard is null or empty.

Category:
Security

Cause:
An empty or null trust group wildcard was passed, but this is not supported.

Action:
Modify the code to pass a non-null and non-empty trust group wildcard.

BEA-099096
An invalid entry {1} found in the group JKS keystore {0}.

Category:
Security

Cause:
Examine the nested exception for more information in diagnosing the problem.

Action:
Verify that the file is a group JKS keystore.

BEA-099097
The group {0} is not in the specified file {1}.

Category:
Security

Cause:
The group is not contained in a group JKS keystore.

Action:
Verify that the group is contained in a group JKS keystore.

BEA-099098
The security provider already has a certificate registered for trust group {0} under the alias {1}.

Category:
Security

Cause:
The certificate alias {0} already exists in the trust group {0}.

Action:
Pass in another certificate alias.

BEA-099099
Errors occurred when register certificate into groups {0}, please see nested message for details.

Category:
Security

Cause:
Errors occurred when trying to register certificates into trust groups.

Action:
Remove the trust group from the passed in trust group list.

BEA-099100
The trust group is null or empty.

Category:
Security

Cause:
An empty or null trust group was used, but this is not supported.

Action:
Modify the code to pass a non-null and non-empty trust group.

BEA-099101
The trust group name {0} is reserved for internal use, please choose another trust group name.

Category:
Security

Cause:
The trust group name is reserved.

Action:
Modify the code to pass another trust group name.

BEA-099102
Subject DN {1} already registered under the alias {2} trust group {0}.

Category:
Security

Cause:
A certificate with subject DN {1} already exists in the trust group {0} under the alias {2}.

Action:
Either remove the previous certificate from the trust group {0} or register a different certificate.

BEA-099103
Issuer DN {1} and serial number {2} already registered under the alias {3} in the trust group {0}

Category:
Security

Cause:
A certificate with issuer DN {1} and serial number {2} already exists in the trust group {0} under the alias {3}.

Action:
Either remove the previous certificate from the trust group {0} or register a different certificate.

BEA-099104
Subject key identifier {1} already registered under the alias {2} in the trust group {0}.

Category:
Security

Cause:
A certificate with subject key identifier {1} already exists in the trust group {0} under the alias {2}.

Action:
Either remove the previous certificate from the security provider or register a different certificate.

BEA-099105
The file path {0} does not exist.

Category:
Security

Cause:
The specified file path does not exist.

Action:
Create the file path {0} or use another existing file path.

BEA-099106
The password is a null or empty string.

Category:
Security

Cause:
The password is a null or empty string.

Action:
Supply a new password which is neither null nor empty.

BEA-099107
The algorithm {0} used to encrypt the file is invalid.

Category:
Security

Cause:
The algorithm {0} used to encrypt the file is invalid.

Action:
Supply a new algorithm.

BEA-099108
Invalid Property file: property "{0}" is required but is not configured.

Category:
Security

Cause:
Invalid Property file: property "{0}" is required but is not configured.

Action:
Add configuration of property "{0}" to your property file.

BEA-099109
Had problem attempting to get CallbackHandler for debugging in {0}: {1}

Category:
Security

Cause:
The system property weblogic.security.DumpContextHandler was set to true, but no CallbackHandler is available to handle the callback.

Action:
If using programmatic authentication, check if the passed CallbackHandler supports handling weblogic.security.auth.callback.ContextHandlerCallback. Otherwise, contact My Oracle Support.

BEA-099110
The value configured for NameMapper attribute: {0} is not valid.

Category:
Security

Cause:
The name mapper class {0} is not in the classpath or it does not implement thename mapper interface.

Action:
Ensure that the name mapper class {0} is in the classpath and implements the name mapper interface.

BEA-099111
The KerberosCredentialMapper could not get credentials. The requestor is {0}. The initiator is {1}. The resource is {2}. The exception is {3}.

Category:
Security

Cause:
An unexpected exception occurred when trying to get the credentials.

Action:
Read the exception text from the log message for more information on diagnosing the problem.

BEA-099112
The KerberosCredentialMapper could not get credentials for initiator with String type. The requestor is {0}. The initiator is {1}. The resource is {2}.

Category:
Security

Cause:
The initiator should not be a String while acquiring credentials with KerberosCredentialMapperProvider.

Action:
Try the getCredentials() method with a Subject as the initiator.

BEA-099113
Illegal parameter type.

Category:
Security

Cause:
An initiator with String type is not supported by NegotaiteCredentialMapper for method getCredential().

Action:
Try the method getCredentials() with Subject as the initiator type.

BEA-099114
The MaxPasswordLength must not be less than MinAlphaCharacters+MinNumericOrSpecialCharacters.

Category:
Security

Cause:
The MaxPasswordLength is less than MinAlphaCharacters+MinNumericOrSpecialCharacters.

Action:
Change the value and try again.

BEA-099115
The MaxPasswordLength must not be less than MinLowercaseCharacters+MinUppercaseCharacters+MinNumericOrSpecialCharacters.

Category:
Security

Cause:
The MaxPasswordLength is less than MinLowercaseCharacters+MinUppercaseCharacters+MinNumericOrSpecialCharacters.

Action:
Change the value and try again.

BEA-099116
The number of numeric or special characters in a password cannot be less than {0}.

Category:
Security

Cause:
The number of numeric or special characters in the password is less than {0}.

Action:
Add more numeric or special characters into your password.

BEA-099117
The LDAP authentication provider named "{0}" failed to make a connection to LDAP server at {1}://{2}:{3}, the error cause is: {4}.

Category:
Security

Cause:
Exception in making connection to LDAP server by the LDAP authentication provider.

Action:
Check the configured host name and port of the LDAP server for the failed LDAP authentication provider; also check SSL configuration details if SSL is enabled. If the failed provider is not used anymore in the domain, remove it to avoid the warning message. To change the default log interval (600 seconds), use the system property "weblogic.security.providers.authentication.connWarningLogIntervalSeconds". Note: If multiple LDAP providers are configured, the failover mechanism may tolerate failures for some providers.

BEA-099118
The special character "{0}" cannot be the first character of a password.

Category:
Security

Cause:
The special character "{0}" cannot be the first character of a password.

Action:
Change the value and try again.

BEA-099500
Invalid property value: {0}={1}

Category:
Security

Cause:
An exception occurred while processing the value for the specified property.

Action:
Correct the property and restart. This exception should not normally occur as the properties are only used internally.

BEA-099501
Caught exception while evaluating policy expression: {0} associated with: {1}

Category:
Security

Cause:
The evaluate method of the predicate used by the policy failed with a RuntimeException.

Action:
Ensure that parameters which are passed to the predicates in the expression or context are valid.

BEA-099502
An invalid predicate {0} was retrieved from the database. Ensure that the predicate class is in the server classpath.

Category:
Security

Cause:
The class file belonging to the condition was not in the server classpath.

Action:
Update the classpath and restart the server.

BEA-099503
Evaluation of policy associated with role {0} failed because the policy expression contains unregistered predicate: {1}.

Category:
Security

Cause:
The predicate that is specified in the log message is not registered, or the policy is out of date.

Action:
Register the predicate or remove its reference from the policy.

BEA-099504
Evaluation of policy associated with resource {0} failed because the policy expression contains unregistered predicate: {1}.

Category:
Security

Cause:
The predicate that is specified in the log message is not registered, or the policy is out of date.

Action:
Register the predicate, or remove its reference from the policy.

BEA-100000
Invalid call to the deprecated method {0}.

Category:
HTTP Session

Cause:
The method was deprecated in the latest servlet specification.

Action:
Check the specification for an alternative. If not corrected, unpredictable behavior might occur.

BEA-100005
Could not remove session: "{0}".

Category:
HTTP Session

Cause:
An unexpected error occurred while removing the session.

Action:
Check the exception text for the exact error message.

BEA-100006
HTTP session file persistence: storing sessions in directory: {0}.

Category:
HTTP Session

Cause:
This is an informational message.

Action:
Ensure that the directory stores the sessions per the PeristentStoreDir session parameter (weblogic.xml).

BEA-100007
Erasing the directory tree for persistent HTTP sessions: {0}.

Category:
HTTP Session

Cause:
The storage directory is being deleted as a result of session invalidation.

Action:
Ensure that deletion is occurring while removing sessions.

BEA-100008
Cannot delete "{0}".

Category:
HTTP Session

Cause:
The storage directory failed to be deleted.

Action:
Ensure that the permissions on this directory are correct and that the file and directory are not in use by another process.

BEA-100011
An error occurred while serializing session data. Deleting this session.

Category:
HTTP Session

Cause:
This might be due to a change in the class definition or serialVersionUID.

Action:
Check the exception text for the exact error message and take appropriate action.

BEA-100013
{0} not invalidated. The session that was serialized into the file system does not exist.

Category:
HTTP Session

Cause:
The session was not found and does not exist.

Action:
This session might have been deleted by a trigger in another server, which is pointing to the same storage location.

BEA-100015
Deleted file-based session persistent store file: {0}.

Category:
HTTP Session

Cause:
This is an informational message indicating that the storage file is being deleted.

Action:
Ensure that the deletion is consistent with the path defined in the PersistentStoreDir (weblogic.xml)

BEA-100016
Session expiration check failed for: {0}. Invalidating the session expiration check.

Category:
HTTP Session

Cause:
An unexpected error occurred while checking the session for expiration.

Action:
The session will be removed from the persistent store. Check the exception text for the exact error message.

BEA-100018
An error occurred while loading the serialized session data for session {0}.

Category:
HTTP Session

Cause:
An unexpected error occurred.

Action:
Check the exception text for the exact error message. The file could be corrupted.

BEA-100019
The file-based persistent session ID: "{0}" was stored in file: "{1}". File exists: {2}.

Category:
HTTP Session

Cause:
This is an informational message indicating that the session was stored in this path.

Action:
Ensure that the file-based persistent session storage is consistent with the PersistentStoreDir (weblogic.xml).

BEA-100020
Received malformed cookie ID: {0}.

Category:
HTTP Session

Cause:
The cookie could not be parsed properly.

Action:
Check the cookie format and the exception text for the exact problem.

BEA-100022
Session invalidation interval: {0}

Category:
HTTP Session

Cause:
The session invalidation trigger is being created.

Action:
Ensure that the session invalidation interval is consistent with the InvalidationIntervalSecs (weblogic.xml).

BEA-100025
An unexpected error occurred in the HTTP session timeout callback while deleting sessions.

Category:
HTTP Session

Cause:
The invalidation trigger failed unexpectedly while deleting sessions.

Action:
Check the exception message for the probable cause.

BEA-100026
An unexpected error occurred in the HTTP session timeout callback while checking session expiration.

Category:
HTTP Session

Cause:
An unexpected error occurred while checking the sessions for expiration.

Action:
Check the exception text for the exact error message.

BEA-100028
The session data could not be deserialized.

Category:
HTTP Session

Cause:
The session data could not be deserialized.

Action:
Ensure that the object being put into the session is serializable and that the non-transient objects it aggregates are also serializable. If any of the non-transient objects in the entire object graph are not serializable, this error message will occur.

BEA-100030
HTTP session expired. Session ID: {0}

Category:
HTTP Session

Cause:
This is an informational message indicating that the session with ID {0} has expired.

Action:
If the session expired sooner than expected, check the SessionTimeout parameter in the weblogic.xml file.

BEA-100031
An error occurred while unregistering the servlet session runtime MBean: {0}.

Category:
HTTP Session

Cause:
This MBean could not be removed.

Action:
Check the exception text for the exact error message.

BEA-100032
An error occurred while creating a servlet session runtime MBean.

Category:
HTTP Session

Cause:
This MBean could not be created.

Action:
Check the exception text for the exact error message.

BEA-100033
The license for replicated sessions is invalid: {0}. Downgrading sessions to memory, which are not replicated.

Category:
HTTP Session

Cause:
The license was not valid to support replicated sessions.

Action:
Check the license. An upgrade to a clustering and replication license may be desired. Alternatively, file and JDBC persistence can be used for session store reliability.

BEA-100035
The timer invalidated session ID: {0}, Web application: {1}, because it expired.

Category:
HTTP Session

Cause:
This message was logged by the Web application level timer, which periodically checks the sessions for expiration. The session expired.

Action:
If the session expired too soon, check the SessionTimeout in the weblogic.xml file.

BEA-100038
Unknown persistent type: {0} for Web application: {1}. Valid types are: memory, file, replicated, JDBC, cookie, and replicated_if_clustered.

Category:
HTTP Session

Cause:
The specified persistent store type for this Web application was not recognized.

Action:
Check the PersistentStoreType parameter in the weblogic.xml file. The valid values are: memory, file, replicated, cookie, JDBC, and replicated_if_clustered.

BEA-100039
Replicated HTTP sessions were specified for the Web application: {0}, but clustering was not enabled.

Category:
HTTP Session

Cause:
The session replication mechanism relies on clustering, which was not been configured.

Action:
Set up clustering or change the PersistentStoreType in the weblogic.xml file to either memory, file, JDBC, or cookie.

BEA-100040
The getAttribute(): {0} was a handle. Reconstructing the EJB object.

Category:
HTTP Session

Cause:
This is an informational message indicating that the container is storing only the handle for the EJB object placed into the session.

Action:
No action is required.

BEA-100041
The setAttribute(): {0} was an EJB object. Storing the handle into the session.

Category:
HTTP Session

Cause:
The container found an EJB handle stored in the session. It will reconstruct the EJB object before returning it.

Action:
No action is required.

BEA-100042
An error occurred while reconstructing the EJB object: {0}, which was put into the session.

Category:
HTTP Session

Cause:
The container found an EJB handle stored in the session. However, it failed to reconstruct the EJB object using that handle.

Action:
Ensure that the handle is still valid. Check the exception text for the exact error message.

BEA-100043
An error occurred while finding the handle for the EJB object: {0}.

Category:
HTTP Session

Cause:
The container stores only the handle for an EJB object put into the session. However, in this case, it failed to find the handle.

Action:
Check the RemoteException for the exact error message details.

BEA-100044
Found WLCookie cookie {0}={1}.

Category:
HTTP Session

Cause:
The cookie persistence mechanism relies on setting the cookie header.

Action:
No action is required.

BEA-100045
Malformed WLCookie. Value: {0} will be ignored.

Category:
HTTP Session

Cause:
The cookie persistence mechanism relies on setting the cookie header.

Action:
The cookie was found to be malformed. Only strings are supported for cookie-based persistence. Ensure that there are no characters in the attribute names and values, which can break the cookie syntax.

BEA-100046
Creating new session with ID: {0} for Web application: {1}.

Category:
HTTP Session

Cause:
A new session was created.

Action:
Ensure that the length is equal to the IDLen parameter in the weblogic.xml file.

BEA-100047
Performing the database operation: {0} with ID: {1} and Web application: {2}.

Category:
HTTP Session

Cause:
This is an informational message for JDBC-based persistence. It is meant for debugging purposes only.

Action:
No action is required.

BEA-100048
Looked up ROID: {0} from host {1}:{2} for ID: {3}.

Category:
HTTP Session

Cause:
The replicated session ID was not found in the current server, perhaps because this server is not the primary or secondary server. Another attempt to retrieve the session from the assigned secondary server will be made if it is alive.

Action:
No action is required.

BEA-100050
The current server is becoming the primary server for replicated session ID: {0}.

Category:
HTTP Session

Cause:
The current server is taking the role of the primary server for the given session.

Action:
No action is required.

BEA-100051
The current server is becoming the secondary server for replicated session ID: {0}.

Category:
HTTP Session

Cause:
The current server is taking the role of the secondary server for the given session.

Action:
No action is required.

BEA-100052
Unregistering replicated session ID: {0}.

Category:
HTTP Session

Cause:
The current server will unregister the given session.

Action:
The session was invalidated. No action is required.

BEA-100053
Failed to update the secondary server for HTTP session ID: {0}.

Category:
HTTP Session

Cause:
Failed to update the secondary server for the modification that occurred in the current request.

Action:
Verify that the secondary server is alive, and ensure that the objects put into the session are all serializable. Also, check the exception text for the exact error message.

BEA-100054
Failed to find the secondary server for HTTP session ID: {0}.

Category:
HTTP Session

Cause:
The secondary server could not be found for the replicated session.

Action:
Verify that the clustering is configured properly and that there is more than one server in the cluster.

BEA-100055
The generated session ID: {0} contains a reserved keyword and is regenerating.

Category:
HTTP Session

Cause:
On Windows 32-bit systems, if the session ID contains a reserved keyword, the file-based persistence fails. This is because it relies upon successful creation of subdirectories. The reserved keywords are: "CON", "PRN", "AUX", "NUL" "COM1", "COM2", "COM3", " COM4", "COM5", "COM6", "COM7", " COM8", "COM9", "LPT1", "LPT2", " LPT3", "LPT4", "LPT5", "LPT6", " LPT7", "LPT8", "LPT9", "CLOCK$"

Action:
No action is required. The session ID will be regenerated.

BEA-100056
For {0}: The session with ID: {1} was invalidated before the session creation and registration could complete.

Category:
HTTP Session

Cause:
This is a past-release problem.

Action:
Contact My Oracle Support.

BEA-100057
This server does not have deployment for the Web application with context path: {0}. The callback: {1} failed while replicating the session. Check the configuration; only uniform configurations in a cluster are supported.

Category:
HTTP Session

Cause:
WebLogic Server clustering relies on uniform Web application deployment across the cluster. It seems the Web application was not deployed on all the servers.

Action:
Redeploy the Web application, and ensure that it targets the cluster and all members in the cluster.

BEA-100058
The PersistentStoreType for the Web application with context path: {0} is not replicated. The callback: {1} failed while replicating the session. Check the configuration; only uniform configurations in a cluster are supported.

Category:
HTTP Session

Cause:
WebLogic Server clustering relies on uniform Web application deployment across the cluster. It seems the Web application was not deployed on all the servers with uniform configuration.

Action:
Redeploy the Web application, and ensure that it targets the cluster and all members in the cluster. Also, the PersistentStoreType should be set to "replicated" for all cluster members.

BEA-100059
An unexpected error occurred while cleaning up sessions during undeployment of Web application: {0}.

Category:
HTTP Session

Cause:
The trigger failed to clean up the expired session.

Action:
Check the exception text for the exact error message. When using JDBC-based HTTP session persistence, ensure that the database is set up properly. For file-based persistence, ensure that the permissions on the storage directory are appropriately set.

BEA-100060
An unexpected error occurred while retrieving the session for Web application: {0}.

Category:
HTTP Session

Cause:
The session from persistent store could not be retrieved.

Action:
Check the configuration, and check the exception text for the exact error message. Also, check the WebLogic Server documentation for more details about how to configure session persistence for Web applications.

BEA-100061
Web application: {0} tried to place a non-serializable attribute: {1} into the session: {2}. This attribute will be lost upon redeployment. This message is logged only once per session.

Category:
HTTP Session

Cause:
The session.setAttribute(name, value) was invoked with a non-serializable value for memory-based sessions.

Action:
If the session data should survive redeployment, ensure that all attributes are serializable. Otherwise, the non-serializable data will be lost upon redeployment.

BEA-100062
Web application: {0} tried to place a non-serializable attribute: {1} into the session: {2}. This attribute will be lost upon redeployment or session failover. Also, such attributes will be scoped to the current server only and will not be replicated to the secondary server. This message is logged only once per session.

Category:
HTTP Session

Cause:
The session.setAttribute(name, value) was invoked with a non-serializable value for a replicated session.

Action:
If the session data should survive redeployment and session failovers, ensure that all attributes are serializable. Otherwise, the non-serializable data will be lost upon failover and redeployment.

BEA-100063
Web application: {0} tried to place a non-serializable attribute: {1} into the session: {2}. This attribute will be lost upon redeployment or session failover. Also, such attributes will be scoped to the current server only and will not be persisted to the disk. This message is logged only once per session.

Category:
HTTP Session

Cause:
The session.setAttribute(name, value) was invoked with a non-serializable value for a file-based persistent session.

Action:
If the session data should survive redeployment and session failovers, ensure that all the attributes are serializable. Otherwise, the non-serializable data will be lost upon failover and redeployment.

BEA-100064
Web application: {0} tried to place a non-serializable attribute: {1} into the session: {2}. The attribute will be lost upon redeployment or session failover. Also, such attributes will be scoped to the current server only and will not be persisted to the database. This message is logged only once per session.

Category:
HTTP Session

Cause:
The session.setAttribute(name, value) attribute was invoked with a non-serializable value for a JDBC-based persistent session.

Action:
If the session data should survive redeployment and session failovers, ensure that all the attributes are serializable. Otherwise, the non-serializable data will be lost upon failover and redeployment.

BEA-100065
{0}. Failed to remove attributes for HTTP session ID: {1}.

Category:
HTTP Session

Cause:
An unexpected error occurred during HTTP session invalidation.

Action:
Check the error message for the exact cause.

BEA-100066
Failed to look up the replicated session object for Web application: {0}, session ID: {1}.

Category:
HTTP Session

Cause:
The ReplicationManager returned the NotFoundException.

Action:
This happens if the object has been cleaned up underneath or the version number does not match with the secondary object. This should not happen normally. Unwanted failovers at the front end can cause unnecessary session failovers in the back end, which could result in this error in certain situations. Check the error message for more information.

BEA-100067
Failed to look up the secondary information for Web application: {0} session ID: {1}.

Category:
HTTP Session

Cause:
The ReplicationManager returned the NotFoundException. This happens if the object has been cleaned up underneath or the version number does not match with the secondary object. This should not happen normally. Unwanted failovers at the front end can cause unnecessary session failovers in the back end, which could result in this error in certain situations.

Action:
Check the error message for more information.

BEA-100068
Failed to look up the secondary information for Web application: {0} session ID: {1}.

Category:
HTTP Session

Cause:
The ReplicationManager failed to look up the secondary information for a valid session.

Action:
This is an unexpected error. Check the error message for details.

BEA-100069
The getAttribute(): {0} was a HomeHandle, reconstructing the EJBHome.

Category:
HTTP Session

Cause:
This is an informational message indicating that the container is storing only the handle for the EJBHome placed into the session.

Action:
No action is required.

BEA-100070
Error reconstructing the EJBHome put into session for name: {0}

Category:
HTTP Session

Cause:
The container found an EJBHome handle stored in the session. However, it failed to reconstruct the EJBHome using that EJBHome handle.

Action:
Ensure that the HomeHandle is still valid. Check the exception text for the exact error message.

BEA-100071
The setAttribute(): {0} was an EJBHome, storing the HomeHandle into the session.

Category:
HTTP Session

Cause:
The container found an EJBHome handle stored in the session. It will reconstruct the EJBHome object before returning.

Action:
No action is required.

BEA-100072
Error in finding the HomeHandle for the EJBHome: {0}.

Category:
HTTP Session

Cause:
The container stores only the handle for an EJBHome put into the session. However, in this case, it failed to find the HomeHandle.

Action:
Check the RemoteException for the exact error message details.

BEA-100073
Exception while serializing session object: {0}.

Category:
HTTP Session

Cause:
The session object failed to serialize.

Action:
Check the exception text for the exact error message details.

BEA-100079
WAN failover configuration missing.

Category:
HTTP Session

Cause:
The JDBCTxDataSource or the backup cluster address was not properly configured.

Action:
Set the JDBCTxDataSource or the backup cluster address to store session state.

BEA-100081
Persistent store settings cannot be changed between versions. The persistent store settings for application {0} is different from the settings for previous versions.

Category:
HTTP Session

Cause:
The persistent store settings of the new version were different from previous versions.

Action:
Ensure that the persistent store settings are not changed when deploying a new version of an application.

BEA-100082
Failed to deploy {0} because the JDBC data source was missing. Target a JDBC data source to the cluster.

Category:
HTTP Session

Cause:
The configuration was incomplete.

Action:
Target a JDBC data source to the cluster. Refer to the cluster documentation for more information.

BEA-100083
The Web application: {0} in application: {1} has its PersistenceStoreType set to: {2} for HTTP sessions. However, the target list does not contain all members of cluster: {3}. Non-homogeneous deployment for replicated sessions is not allowed.

Category:
HTTP Session

Cause:
Non-homogeneous deployment for replicated sessions is not allowed. The target list must be a cluster or a virtual host which is targeted to a cluster.

Action:
Fix the targets for this Web application. Specify a cluster or virtual host as the target.

BEA-100084
The Web application: {0} in application: {1} has its PersistenceStoreType set to: {2} for HTTP sessions. However, the target list contains virtual host: {3}, for which the target list does not contain all members of cluster: {4}. Non-homogeneous deployment for replicated sessions is not allowed.

Category:
HTTP Session

Cause:
Non-homogeneous deployment for replicated sessions is not allowed. The target list must be a cluster or a virtual host which is targeted to a cluster.

Action:
Fix the targets for this Web application.Specify a cluster or virtual host as the target.

BEA-100087
The JDBC session data for session ID: {0} has been modified by another server in the cluster.

Category:
HTTP Session

Cause:
The front-end Web server failed to maintain server affinity.

Action:
Ensure that the front-end Web server or load balancer has been properly configured.

BEA-100089
The session ID: {0} has been accessed from {1}, a server that is neither the primary ({2}) nor the secondary ({3}). The request URL was: {4}

Category:
HTTP Session

Cause:
The most likely cause is a configuration error on a front end hardware loadbalancer or webserver plugin. They should be configured to respect the values of primary/secondary in the cookie (i.e., stickiness), when possible.

Action:
Please ensure that the front end webserver or load-balancer has been properly configured.

BEA-100090
An unexpected error occurred during a batched update of the last accessed time attribute of the updated sessions in application {0}.

Category:
HTTP Session

Cause:
Check the exception message for details.

Action:
Check the exception message for details.

BEA-100094
The session ID: {0} has been accessed from {1}, a server that is not the primary ({2}). The request URL was: {3}.

Category:
HTTP Session

Cause:
The most likely cause is a configuration error on a front-end hardware load balancer or Web server plug-in. These should be configured to respect the values of the primary or secondary in the cookie (for example, stickiness), when possible.

Action:
Ensure that the front-end Web server or load balancer has been properly configured.

BEA-100095
persistent-data-source-jndi-name is required for an async-jdbc session.

Category:
HTTP Session

Cause:
persistent-data-source-jndi-name was not used to specify the data source JNDI name for the JDBC connection, but persistent-store-type is async-jdbc.

Action:
Use persistent-data-source-jndi-name to specify the data source JNDI name for the JDBC connection.

BEA-100096
persistent-data-source-jndi-name will take effect and persistent-store-pool will be ignored for async-jdbc session in application {0}.

Category:
HTTP Session

Cause:
This is debug information.

Action:
No action is required.

BEA-100097
The IDLength {0} is too short. It is not secure. WebLogic Server will increase the length to {1}.

Category:
HTTP Session

Cause:
The IDLength of Session Descriptor is smaller than {1}.

Action:
Mofify the Weblgoic deployment descriptor. Ensure that the IDLength of Session Descriptor is equal to or greater than {1}.

BEA-100098
persistent-data-source-jndi-name or persistent-store-pool is required when persistent-store-type is jdbc.

Category:
HTTP Session

Cause:
persistent-data-source-jndi-name or persistent-store-pool was not used to configure the database connection, but persistent-store-type is jdbc.

Action:
Use persistent-data-source-jndi-name or persistent-store-pool to configure the database connection.

BEA-100099
An error occurred while looking up the session with ID:{0} from primary server:{1} and secondary server:{2}.

Category:
HTTP Session

Cause:
A RemoteException occurred when looking up the session from the secondary server.

Action:
Check if the secondary server is down. Note that it is not recommended to stop both the primary and secondary server at the same time. Because replication happens lazily, upon request, if the secondary server needs to end, give sufficient time so that the active end users hit their sessions and get replicated.

BEA-100100
Replication services could not be found for remote object {1} in application context {0}.

Category:
HTTP Session

Cause:
This error can occur during clustered application undeployment or redeployment, particularly when the server where it occurs is configured for managed server independent deployment (MSI-D). It is typically transient in those situations, and should only occur during redeployment in those scenarios.

Action:
If the error persists, check the server log files for more details. Contact Oracle support if necessary.

BEA-101002
[{0}] Could not deserialize the context attribute.

Category:
HTTP

Cause:
The classloader changed. When this happens, the old attributes are deserialized using the new classloader.

Action:
Ensure that the attribute class is available to the Web application scope and is serializable.

BEA-101003
[{0}] {1} called with a null document root.

Category:
HTTP

Cause:
The Web application did not initialize correctly.

Action:
Check the log file for error messages about this Web application.

BEA-101005
[{0}] {1} called with unsafe path: "{2}".

Category:
HTTP

Cause:
The virtual path that was passed in points to a resource outside of the Web application scope.

Action:
Check the virtual path being passed to the method and rectify the problem accordingly.

BEA-101008
[{0}] Cannot get InputStream of resource "{1}".

Category:
HTTP

Cause:
The getResourceAsStream() method failed to get an InputSteam for the resource.

Action:
Ensure that the resource exists.

BEA-101017
[{0}] Root cause of ServletException.

Category:
HTTP

Cause:
The Web application container caught an unexpected exception.

Action:
Check the exception for the exact error message.

BEA-101019
[{0}] Servlet failed with an IOException.

Category:
HTTP

Cause:
An unexpected IOException was caught while processing the request.

Action:
Check the exception for the exact error message.

BEA-101020
[{0}] Servlet failed with an Exception

Category:
HTTP

Cause:
An unexpected error occurred.

Action:
Check the exception for the exact error message.

BEA-101024
[{0}] Unsupported error status code for the error-page element in web.xml.

Category:
HTTP

Cause:
The format of the error status code was invalid.

Action:
Check the web.xml and fix the error-page element error status code.

BEA-101025
[{0}] Document root is null.

Category:
HTTP

Cause:
This should never happen. The initialization failed.

Action:
Check the log file for error messages during the Web application initialization phase.

BEA-101027
[{0}] Document root: "{1}" does not exist.

Category:
HTTP

Cause:
This is an unexpected error message.

Action:
Ensure that the directory exists.

BEA-101029
[{0}] cannot make temporary directory "{1}". Will not be able to compile JSPs.

Category:
HTTP

Cause:
The creation of the temporary directory failed.

Action:
Check the write permissions.

BEA-101040
[{0}] Error occurred while trying to set "{1}{2}".

Category:
HTTP

Cause:
A NumberFormatException occurred while parsing the value assigned to the reloadCheckSecs parameter in web.xml.

Action:
Ensure that the value was entered correctly.

BEA-101045
[{0}] {1}

Category:
HTTP

Cause:
This is a general purpose error message.

Action:
Check the message for the exact cause and take proper action.

BEA-101046
[{0}] {1}

Category:
HTTP

Cause:
This is a general purpose error message.

Action:
Check the exception for exact cause and take proper action.

BEA-101047
[{0}] {1}

Category:
HTTP

Cause:
This is a general purpose informational message for debug purposes only.

Action:
This is a debug message. No action is required.

BEA-101051
[{0}] started

Category:
HTTP

Cause:
This is an informational message indicating that the Web server has been started.

Action:
This is a debug message. No action is required.

BEA-101052
[{0}] Initialized

Category:
HTTP

Cause:
This is an informational message indicating that the Web server has been initialized.

Action:
This is a debug message. No action is required.

BEA-101053
[{0}] Loading Web application: {1}

Category:
HTTP

Cause:
The Web application is being deployed.

Action:
This is a debug message. No action is required.

BEA-101054
[{0}] {1} is the default Web application for {2}.

Category:
HTTP

Cause:
The given Web application is being registered as a default Web application.

Action:
This is a debug message. No action is required.

BEA-101060
[{0}] Loading "{1}" from directory: "{2}"

Category:
HTTP

Cause:
The Web application was deployed using an exploded directory structure.

Action:
This is a debug message. No action is required.

BEA-101061
[{0}] Could not find Web application "{1}".

Category:
HTTP

Cause:
The descriptor for the Web application with the name given could not be loaded.

Action:
Check the error message for details and ensure that the Web application was configured properly.

BEA-101062
[{0}] Error reading Web application "{1}".

Category:
HTTP

Cause:
An IOException occurred while reading the descriptors for the Web application.

Action:
Ensure that the web.xml and weblogic.xml descriptors exist in the right place.

BEA-101064
[{0}] Error parsing descriptor in Web appplication "{1}"

Category:
HTTP

Cause:
An unexpected error occurred while reading the descriptors for the Web application.

Action:
Ensure that web.xml and weblogic.xml exist in the right place

BEA-101066
[{0}] Cannot initialize HTTP URL resources. Could not get JNDI context: {1}.

Category:
HTTP

Cause:
The URL contexts could not be registered because the JNDI context was not found.

Action:
Ensure that the JNDI resources were properly configured.

BEA-101067
[{0}] Disregarding null URL resource value for property {1}

Category:
HTTP

Cause:
The URL for the JNDI resource specified in URLResource was null.

Action:
Correct the configuration (WebServerMBean). The URLs cannot be null.

BEA-101068
[{0}] Could not parse URL resource value {1}.

Category:
HTTP

Cause:
The URL for the JNDI resource specified in the URL resource was malformed.

Action:
Correct the configuration (WebServerMBean). Specify a valid URL.

BEA-101069
[{0}] Could not bind URL {1} to JNDI name {2} error message: {3}.

Category:
HTTP

Cause:
The URL failed to bind with the JNDI name.

Action:
Correct the configuration (WebServerMBean).

BEA-101070
[{0}] Bound URL resource "{1}" to JNDI name "{2}".

Category:
HTTP

Cause:
This is an informational message only.

Action:
No action is required.

BEA-101075
[{0}] HttpServer is shutting down.

Category:
HTTP

Cause:
The Web server is shutting down.

Action:
This is a debug message. No action is required.

BEA-101083
Connection failure.

Category:
HTTP

Cause:
The connection failed while writing data into the stream.

Action:
Check the exception for the exact cause and take appropriate action.

BEA-101086
No host in HTTP header. Dispatching to default HTTP server.

Category:
HTTP

Cause:
Host header missing.

Action:
Ensure that the requests are accompanied with a host header in order for virtual hosting to work. Also, proper HTTP redirects must have a host header.

BEA-101087
{0} is not a virtual host. Dispatching to default HTTP server.

Category:
HTTP

Cause:
The host header is missing from the HTTP request.

Action:
Make sure the requests are accompanied with a host header in order for Virtual Hosting to work. Also, proper HTTP redirects must have a host header.

BEA-101088
Dispatching request to {0}.

Category:
HTTP

Cause:
Dispatching the request to the Web server (Virtual Host) defined by the host header.

Action:
Check the configuration.

BEA-101093
A problem occurred while dispatching the servlet request.

Category:
HTTP

Cause:
The request could not be dispatched into the execute queue.

Action:
The request could be malformed. Check the exception for the exact cause.

BEA-101095
POST time exceeded the configured MaxPostTimeSecs of {0,number}.

Category:
HTTP

Cause:
The parameter makes sure that a malicious user does not send slow POSTs to cause a denial of service attack.

Action:
If you think the time was too short, try increasing the value of MaxPostTimeSecs using the Administration Console.

BEA-101096
POST size exceeded the MaxPostSize={0,number}.

Category:
HTTP

Cause:
The parameter makes sure that a malicious user does not send huge POSTs to cause a denial of service attack.

Action:
If you think the post size is unreasonable, try increasing MaxPostSize using the Administration Console.

BEA-101100
[{0}] Got bad cookie header: {1} from User-Agent: {2}

Category:
HTTP

Cause:
A cookie was malformed.

Action:
Refer to the cookie specifications for the correct format: http://www.ietf.org/rfc/rfc2965.txt (Oct 2000; Obsoletes: 2109) http://www.ietf.org/rfc/rfc2109.txt (Feb 1997) http://www.ietf.org/rfc/rfc2616.txt (Jun 1999; Obsoletes: 2068) http://www.ietf.org/rfc/rfc2068.txt (Jan 1997)

BEA-101101
[{0}] Unable to create new session.

Category:
HTTP

Cause:
A new session could not be created.

Action:
Ensure that the persistent store has been properly configured.

BEA-101104
Servlet execution in servlet context "{0}" failed, {1}.

Category:
HTTP

Cause:
An unexpected error occurred while serving the request. This is not a simple client connection reset error.

Action:
Check the error message for the exact cause.

BEA-101105
[{0}] error-page location: "{1}" for the error-code: "{2,number}" does not exist. Serving the default error page.

Category:
HTTP

Cause:
The error-page you configured in web.xml does not exist. A configuration error has occurred.

Action:
Correct the web.xml descriptor, or make the resource available.

BEA-101106
[{0}] Could not serve custom error page: "{1}" for the error code: "{2,number}"

Category:
HTTP

Cause:
The error-page configured in web.xml does not exist. A configuration error has occurred.

Action:
Correct the web.xml descriptor or make the resource available.

BEA-101107
[{0}] Problem occurred while serving the error page.

Category:
HTTP

Cause:
The error-page configured in web.xml could not be served.

Action:
Check the configuration in web.xml.

BEA-101108
[{0}] Unsupported encoding: "{1}" specified.

Category:
HTTP

Cause:
The specified encoding is not supported by the underlying virtual machine(VM).

Action:
Ensure that the specified encoding is valid or install the additional encoding classes.

BEA-101122
[{0}] Servlet: "{1}" is permanently unavailable.

Category:
HTTP

Cause:
The Web application is not currently available.

Action:
Ensure that the Web application has been deactivated. Check to see if redeployment is in progress.

BEA-101123
[{0}] Servlet: "{1}" will be unavailable for the next: "{2,number}" seconds.

Category:
HTTP

Cause:
The servlet has been marked as unavailable.

Action:
Make the request again after the specified time.

BEA-101125
[{0}] Error occurred while instantiating servlet: "{1}".

Category:
HTTP

Cause:
The servlet failed to instantiate.

Action:
Ensure that the servlet has been configured properly in web.xml. Also, check the exception for the exact cause.

BEA-101126
[{0}] Error casting servlet: "{1}" to javax.servlet.Servlet

Category:
HTTP

Cause:
The servlet class that has been configured does not implement javax.servlet.Servlet.

Action:
Fix the definition of the class.

BEA-101128
Initializing HTTP services.

Category:
HTTP

Cause:
This is an informational message.

Action:
Ensure that the resources are available now.

BEA-101129
Initializing the Web application container.

Category:
HTTP

Cause:
This is an informational message.

Action:
This is an informational message. No action is required.

BEA-101133
Initializing Web server {0}.

Category:
HTTP

Cause:
The Web server was just initialized.

Action:
No action is required.

BEA-101135
{0} is the default Web server.

Category:
HTTP

Cause:
The default Web server name is being logged.

Action:
This is an informational message for debug purposes only. No action is required.

BEA-101136
Registering virtual host: {0}.

Category:
HTTP

Cause:
A Virtual Host (non-default Web server) has been registered.

Action:
This is an informational message for debug purposes only. No action is required.

BEA-101138
{0} One of the getParameter family of methods was called after reading from the ServletInputStream. Not merging post parameters.

Category:
HTTP

Cause:
If the servlet reads the data from the input stream directly, then the request data will not be available for the getParameter family of methods.

Action:
If the code relies on post parameters being available through the getParameter method, fix the code.

BEA-101140
An error occurred while creating servlet {1} (class: {2}, initArgs: {3}) for Web application {0}.

Category:
HTTP

Cause:
The servlet instance failed to initialize.

Action:
Check the configuration and the exception for the exact error message.

BEA-101142
There was an error unregistering servlet runtime {0}.

Category:
HTTP

Cause:
The servlet runtime MBean that is used for monitoring could not be destroyed.

Action:
Report this problem to My Oracle Support.

BEA-101143
An error occurred while unregistering Web application component runtime {0}.

Category:
HTTP

Cause:
The Web application runtime MBean that is used for monitoring could not be destroyed.

Action:
Report this problem to My Oracle Support.

BEA-101159
[{0}] Received IllegalAccessException while instantiating servlet: "{1}". Ensure that the servlet implementation is a public class.

Category:
HTTP

Cause:
This occurs if WebLogic Server attempts to instantiate a servlet class that is not declared public.

Action:
Ensure that the servlet implementation is a public class.

BEA-101160
Deployment descriptor is malformed; check against the DTD: {0}.

Category:
HTTP

Cause:
The web.xml file is not in strict conformance to the DTD. There may be deployment problems if this is not corrected.

Action:
Check the web.xml file against the DTD to ensure conformance. Remember that the ordering of elements is important.

BEA-101162
User defined listener {0} failed: {1}.

Category:
HTTP

Cause:
The listener failed while processing the event fired by the container.

Action:
Check the exception for the exact error message and fix the listener code.

BEA-101163
Could not load user defined listener: {0}

Category:
HTTP

Cause:
The listener class could not be loaded or instantiated.

Action:
Check the exception for the exact error message and fix the listener code.

BEA-101164
User defined class {0} is not a listener, as it does not implement the correct interface(s).

Category:
HTTP

Cause:
The class is invalid.

Action:
Fix the listener code to implement the appropriate interfaces.

BEA-101165
Could not load user defined filter in web.xml: {0}.

Category:
HTTP

Cause:
The filter class could not be loaded.

Action:
Check the configuration and ensure that the class is available to the context classloader.

BEA-101168
The security-role-assignment references an invalid security-role: {0}.

Category:
HTTP

Cause:
The security-role-assignment specified in weblogic.xml is not valid.

Action:
Ensure that the role-name defined in web.xml is valid. Also, check the DTD and examples for the correct syntax.

BEA-101169
The servlet {0} is referenced but not defined in web.xml.

Category:
HTTP

Cause:
The servlet-mapping element in web.xml refers to a servlet name that was not defined.

Action:
Ensure that the servlet-name that is used for the mapping is defined. Check the DTD for the correct syntax.

BEA-101170
The servlet {0} is referenced in servlet-mapping {1} but not defined in web.xml.

Category:
HTTP

Cause:
The servlet-mapping element in web.xml refers to a servlet name that was not defined.

Action:
Ensure that the servlet-name that is used for the mapping is defined. Check the DTD for the correct syntax.

BEA-101171
The web.xml descriptor has no resource-ref entries for the reference-descriptor defined in weblogic.xml.

Category:
HTTP

Cause:
The resource-ref-name referred to by the reference-descriptor in weblogic.xml should have a corresponding resource-ref-name defined in web.xml.

Action:
Ensure that the resource-ref-name matches a resource-ref-name defined in web.xml.

BEA-101172
The web.xml descriptor has no ejb-ref entries.

Category:
HTTP

Cause:
The ejb-ref-name referred to by the reference-descriptor in weblogic.xml should have a corresponding ejb-ref-name defined in web.xml.

Action:
Ensure that the ejb-ref-name matches a ejb-ref-name defined in web.xml.

BEA-101173
Did not find resource-ref in web.xml matching {0}.

Category:
HTTP

Cause:
The resource-ref-name referred to by the reference-descriptor in weblogic.xml should have a corresponding resource-ref-name defined in web.xml.

Action:
Ensure that the resource-ref-name matches a resource-ref-name defined in web.xml.

BEA-101174
Did not find ejb-ref in web.xml matching {0}.

Category:
HTTP

Cause:
The ejb-ref-name referred to by the reference-descriptor in weblogic.xml should have a corresponding ejb-ref-name defined in web.xml.

Action:
Ensure that the ejb-ref-name matches a ejb-ref-name defined in web.xml.

BEA-101175
[{0}] Exception occurred while closing zip file {1}.

Category:
HTTP

Cause:
A zip file failed to close while undeploying a Web application.

Action:
Report this problem to My Oracle Support.

BEA-101180
The auth-constraint references security-role: {0}, which is not defined in web.xml.

Category:
HTTP

Cause:
The auth-constraint should refer to roles that have been defined in web.xml.

Action:
Add the definition of this role in the security-role element of web.xml.

BEA-101188
A bad exception-type exists in web.xml: {0}.

Category:
HTTP

Cause:
An invalid class can cause this exception while registering the Web application.

Action:
Check the classpath.

BEA-101189
Could not load the url-match-map class defined in weblogic.xml: {0}.

Category:
HTTP

Cause:
An invalid classname will cause this exception while registering the Web application.

Action:
Check the classpath.

BEA-101194
The preprocessor {0} is referenced but not defined in weblogic.xml.

Category:
HTTP

Cause:
The preprocessor element is not defined in weblogic.xml.

Action:
Check the weblogic.xml descriptor.

BEA-101196
[{0}]: Error while parsing the Tag Library Descriptor at "{1}".

Category:
HTTP

Cause:
A TLD parsing exception occurred.

Action:
Check the exception for the exact cause.

BEA-101198
Could not deploy role: {0} for Web application: {1} application: {2}.

Category:
HTTP

Cause:
The Web application could not deploy the role defined in web.xml.

Action:
Ensure that security is configured properly in the server. Also, check the stack trace for the exact cause.

BEA-101199
Could not deploy policy for resource: {0}.

Category:
HTTP

Cause:
The Web application failed to deploy the policy for the security-constraint defined in web.xml.

Action:
Ensure that security is configured properly in the server. Also, check the stack trace for the exact cause.

BEA-101200
CacheFilter not caching the response for URI: {0} reason: {1}

Category:
HTTP

Cause:
The CacheFilter does not cache responses unless the status is 200.

Action:
Check the message for information on how to fix the problem.

BEA-101212
{0}:{1} Failure while precompiling JSPs: {2}.

Category:
HTTP

Cause:
The JSPs failed to precompile at startup.

Action:
Check the exception for the exact cause.

BEA-101214
Included resource or file "{0}" not found from requested resource "{1}".

Category:
HTTP

Cause:
The included resource or file is missing.

Action:
Add the missing resource or file.

BEA-101215
Malformed request "{0}". Request parsing failed, Code: {1}

Category:
HTTP

Cause:
The request does not follow the pattern specified by the HTTP 1.0/1.1 specification(s).

Action:
Fix the client that sent the invalid request.

BEA-101216
Servlet: "{0}" failed to preload on startup in Web application: "{1}".

Category:
HTTP

Cause:
The servlet that was marked as load-on-startup failed to preload on startup.

Action:
Check the exception for the exact cause.

BEA-101217
Cannot deploy {0} from {1} on {2}, because there is already a Web application named {3} loaded from {4}, using the context path {5}.

Category:
HTTP

Cause:
The Web application that is being deployed has been assigned a context path that is already in use.

Action:
Choose a different context path.

BEA-101218
An error exists in web.xml for servlet "{0}". Neither servlet-class nor jsp-file is defined.

Category:
HTTP

Cause:
The servlet element should contain either servlet-class or jsp-file. Both are missing.

Action:
Update the web.xml descriptor.

BEA-101220
An error occurred while setting the document root for "{0}" to "{1}".

Category:
HTTP

Cause:
Setting the document root for the Web application failed. The Web application will not be deployed.

Action:
Check the IOException message for exact cause of the problem.

BEA-101221
The url-pattern is empty or null for url-pattern {0} in {1}.

Category:
HTTP

Cause:
Not a valid url-pattern for the servlet.

Action:
If the servlet is intended to be a default servlet, then specify / or /*.

BEA-101223
{0}: The server {1} is temporarily suspended.

Category:
HTTP

Cause:
The server has been suspended by the administrator.

Action:
Wait until it comes back up again.

BEA-101226
AuthFilter: {0} invocation failed in: {1} phase for URI: {2}

Category:
HTTP

Cause:
The authentication filter that acts before and after the authentication phase failed to execute.

Action:
Check the exception for the exact cause of the problem.

BEA-101228
Failed to undeploy security policy for resource: {0} while undeploying Web application.

Category:
HTTP

Cause:
The security policy defined in web.xml failed to undeploy upon Web application undeployment.

Action:
Check the exception for the exact cause of the problem.

BEA-101229
Failed to undeploy security policy for resource: {0} while undeploying the Web application.

Category:
HTTP

Cause:
The security role defined in web.xml failed to undeploy upon Web application undeployment.

Action:
Check the exception for the exact cause of the problem.

BEA-101231
The HTTP log file does not use version 1.0 of the Extended Log File format.

Category:
HTTP

Cause:
The ELF headers in the existing log file specify a version other than 1.0.

Action:
Only version 1.0 is supported. Delete the existing log file and start over again.

BEA-101232
An exception occurred while reading headers of HTTP log file.

Category:
HTTP

Cause:
An IOException was received while reading the headers.

Action:
Check the exception for the exact cause of the problem.

BEA-101234
Attempting to initialize ExtendedLogFormat application specific header: {0}. However, initialization failed due to an exception.

Category:
HTTP

Cause:
An unexpected error occurred while initializing the log file format.

Action:
Check the exception for the exact error message.

BEA-101235
Attempting to initialize ExtendedLogFormat application specific header: {0}. However, initialization failed because class: {1} is not an instance of weblogic.servlet.logging.CustomELFLogger.

Category:
HTTP

Cause:
An unexpected error occurred while initializing the ExtendedLogFormat.

Action:
Check the exception for the exact error message.

BEA-101236
The format of log field {0} is incorrect.

Category:
HTTP

Cause:
The format of the log field is invalid.

Action:
Check the log field and fix the format.

BEA-101237
HTTP logging has been disabled for the Web server: {0}.

Category:
HTTP

Cause:
This is a debug message.

Action:
No action is required.

BEA-101242
Failed to roll the HTTP log file for the Web server: {0}.

Category:
HTTP

Cause:
An unexpected error occurred.

Action:
Check the exception message for the exact cause.

BEA-101247
{0}: Public ID references the old version of the Servlet DTD. Change the public ID in web.xml file to "{1}".

Category:
HTTP

Cause:
The public ID in WEB-INF/web.xml references the old version of servlet DTD.

Action:
Generally, this will not cause any problems with the application unless the DTD has changed in a way such that the web.xml cannot be parsed. To avoid the message, change the public ID in the web.xml file to the current version of the servlet DTD.

BEA-101248
[{0}]: Deployment descriptor "{1}" is malformed. Check against the DTD: {4} (line {2}, column {3}).

Category:
HTTP

Cause:
The descriptor file is not in strict conformance to its DTD. There may be deployment problems if this is not corrected.

Action:
Check the descriptor file against the DTD to ensure conformance. Remember that the ordering of elements is important.

BEA-101249
[{0}]: Servlet class {2} for servlet {1} could not be loaded because the requested class was not found in the classpath {3}. {4}.

Category:
HTTP

Cause:
The servlet class was not recognized by the Web application classloader.

Action:
Ensure that the servlet class is available either in WEB-INF/classes or WEB-INF/lib or the system classpath.

BEA-101250
[{0}]: Servlet class {2} for servlet {1} could not be loaded because a class on which it depends was not found in the classpath {3}. {4}.

Category:
HTTP

Cause:
One of the classes the servlet class uses was not recognized by the Web application classloader.

Action:
Make sure the class is available either in WEB-INF/classes or WEB-INF/lib or system classpath.

BEA-101251
[{0}]: Could not load servlet class {2} for servlet {1} because a resource on which it depends was not found in the classpath {3}. {4}.

Category:
HTTP

Cause:
This exception occurs if the Java Virtual Machine (JVM) cannot find an appropriate native-language definition of a method that is declared native.

Action:
This could be due to a problem with path/LD_LIBRARY_PATH. Check if the resource it complains about exists.

BEA-101252
[{0}]: Servlet class {2} for servlet {1} could not be verified. {3}.

Category:
HTTP

Cause:
This exception occurs when the "verifier" detects that a class file, though well formed, contains some sort of internal inconsistency or security problem.

Action:
Verify the servlet class.

BEA-101253
[{0}]: Servlet class {2} for servlet {1} could not be defined. The class file could be corrupt. {3}.

Category:
HTTP

Cause:
This exception occurs when the Java Virtual Machine (JVM) attempts to read a class file and determines that the file is malformed or otherwise cannot be interpreted as a class file.

Action:
Check to see if the class file is corrupt.

BEA-101254
[{0}]: Servlet class {2} for servlet {1} could not be handled by the classloader with classpath {3}. {4}.

Category:
HTTP

Cause:
Subclasses of LinkageError indicate that a class has some dependency on another class; however, the latter class has incompatibly changed after the compilation of the former class.

Action:
Check the class and its dependencies.

BEA-101256
The run-as user: {0} for the servlet: {1} for Web application: {2} could not be resolved to a valid user in the system. Verify that the user exists.

Category:
HTTP

Cause:
The run-as element in weblogic.xml refers to an invalid user.

Action:
Check to see if the user exists.

BEA-101257
Failed to parse the client certificate in header: {0}. Ignoring this certificate.

Category:
HTTP

Cause:
The format of the client certificate was invalid.

Action:
Check the exception for more details.

BEA-101258
Invalid JSP parameter in weblogic.xml with name: {0}.

Category:
HTTP

Cause:
The JSP parameter was not recognized.

Action:
Check the weblogic.xml descriptor and refer to the DTD for the correct syntax and element information.

BEA-101260
The JSP parameter name in weblogic.xml is empty.

Category:
HTTP

Cause:
One of the mandatory elements in weblogic.xml was found to be empty.

Action:
Check the weblogic.xml descriptor.

BEA-101261
Invalid session parameter name in weblogic.xml: {0}.

Category:
HTTP

Cause:
One of the session parameters configured in weblogic.xml was invalid.

Action:
Check the weblogic.xml and correct the session parameter.

BEA-101262
The session parameter name "{0}" in weblogic.xml is deprecated.

Category:
HTTP

Cause:
This parameter has been deprecated.

Action:
See the WebLogic Server documentation for an alternative. This parameter might be removed from future releases.

BEA-101263
The session parameter name in weblogic.xml is empty.

Category:
HTTP

Cause:
The param-name element is a mandatory element.

Action:
Check the weblogic.xml descriptor.

BEA-101264
{0}: CLIENT-CERT-based authentication failed.

Category:
HTTP

Cause:
Authentication failed.

Action:
Either the certificate was missing or the user the certificate resolves to is not a valid user in the system.

BEA-101267
Failed while destroying filter: {0}.

Category:
HTTP

Cause:
Destroying the filter on the Web application undeploy failed.

Action:
There might be a problem in the implementation of the destroy method. Check the exception for the exact cause.

BEA-101268
{0}: Failed while destroying servlet: {1}.

Category:
HTTP

Cause:
Destroying a servlet on the Web application undeploy failed.

Action:
There might be a problem in the implementation of the destroy method. Check the exception for the exact cause.

BEA-101271
The url-pattern element is not specified for the web-resource-collection/web-resource-name: {0} in the web.xml descriptor.

Category:
HTTP

Cause:
The url-pattern element is a mandatory element.

Action:
If you want the security constraint to apply for all requests, specify url-pattern=/*.

BEA-101275
Server has detected non-replicated sessions while SUSPENDING. Server will wait for non-replicated sessions to either become invalidated or timed out or will wait until a secondary is chosen using the lazy process (meaning if a session does not have a secondary, the server waits until the next request to create the secondary). The current timeout value is {0} seconds. To terminate non-replicated sessions immediately, use the FORCESHUTDOWN option.

Category:
HTTP

Cause:
During graceful shutdown, the server waits for inflight work to complete. This includes non-replicated sessions.

Action:
No action is required. Use FORCESHUTDOWN to ignore inflight work and force shutdown of the server.

BEA-101276
Web application(s) {1} still have non-replicated sessions after {0} minutes of initiating SUSPEND. Waiting for non-replicated sessions to finish.

Category:
HTTP

Cause:
The server is waiting for sessions to finish before gracefully shutting down.

Action:
No action is required. Use FORCESHUTDOWN to ignore inflight work and shutdown the server.

BEA-101277
Web application(s) {0} has {1} non-replicated session(s) respectively.

Category:
HTTP

Cause:
The server has detected non-replicated sessions while gracefully shutting down.

Action:
No action is required. Use FORCESHUTDOWN to ignore inflight work and shut down the server.

BEA-101278
There are no active sessions. The Web service is ready to suspend.

Category:
HTTP

Cause:
All active sessions have completed. The Web service is ready to gracefully shut down.

Action:
No action is required.

BEA-101280
Failed to create WebServerRuntimeMBean for the Web server: {0}.

Category:
HTTP

Cause:
The Web server creates a runtime MBean during the initialization phase for monitoring.

Action:
Check the exception for the exact cause.

BEA-101282
{0}: jspServlet "{1}" defined in weblogic.xml could not be registered. It should be a subclass of javax.servlet.http.HttpServlet.

Category:
HTTP

Cause:
The user-defined class should be a subclass of javax.servlet.http.HttpServlet.

Action:
The jspServlet class must be a subclass of javax.servlet.http.HttpServlet.

BEA-101283
{0}: jspServlet "{1}" defined in weblogic.xml could not be loaded.

Category:
HTTP

Cause:
The user-defined class was unable to load.

Action:
Ensure that the class appears in the webapp-classpath.

BEA-101287
{0}. The servlet: {1} received an exception during servlet destroy. Ensure that the super.init(config) is called in the init() method.

Category:
HTTP

Cause:
This is due to a bug in javax.servlet.GenericServlet.

Action:
Ensure that the super.init(config) is called in the init() method for the servlet.

BEA-101288
Application:{0} WebAppModule: {1} failed to set contextPath: {2}.

Category:
HTTP

Cause:
The set context path call failed for the MBean.

Action:
Check that the context path assigned to this Web application module is valid.

BEA-101291
The webAppModule: {1} in application: {0} is unable to reload classes because it shares a classloader with other modules.

Category:
HTTP

Cause:
An attempt to reload a class was made when the classloader was shared by other modules.

Action:
Ensure that the module has its own classloader or reload all modules that share the classloader at once.

BEA-101292
Validation failed for the descriptor: {0} param: {1}.

Category:
HTTP

Cause:
The container found an illegal value assigned to this parameter.

Action:
Check the error message for the exact cause.

BEA-101295
Recompiling JSP [{0}], resource [{1}], because it is stale. It was previously compiled using a different version of WebLogic Server. JSP build version: {2} WebLogic Server build version: {3}.

Category:
HTTP

Cause:
A JSP was compiled using a different version of WebLogic Server or JSPC.

Action:
To precompile JSPs, ensure that you precompile them using the same version, service pack, rolling patches, and temporary-patches in your classpath for WebLogic Server or JSPC. This will ensure the same version string and compatibility at runtime.

BEA-101296
Unable to load the default compiler class "{0}". Using the default javac compiler to compile JSPs.

Category:
HTTP

Cause:
The compiler class was not found and hence could not be loaded.

Action:
Ensure that the class exists in the classpath.

BEA-101297
The value assigned to the container-descriptor parameter: index-directory-sort-by in weblogic.xml is invalid: {0}. The valid values are "NAME", "LAST_MODIFIED", or "SIZE".

Category:
HTTP

Cause:
An invalid value is specified in weblogic.xml for the container-descriptor parameter: index-directory-sort-by.

Action:
Fix the values in the weblogic.xml descriptor. Valid values are "NAME", "LAST_MODIFIED", or "SIZE".

BEA-101299
The servlet-mapping for servlet-name "{0}" will override the default mapping for *.jsp. This can lead to a show code vulnerability.

Category:
HTTP

Cause:
The url-pattern *.jsp is being overriden in the web.xml by a user-defined servlet.

Action:
Since the default JSP servlet will be overriden, care must be taken to ensure that JSP source code does not appear directly on the browser.

BEA-101302
Web application: {0}, the {1} role: {2} defined in the descriptor: {3} has not been mapped to a principal name in weblogic.xml. Will use the first principal-name: {4} specified in security-role-assignment as the run-as-identity. The run-as role can be mapped to a principal name in weblogic.xml using either run-as-role-assignment element or the servlet-descriptor/run-as-principal-name.

Category:
HTTP

Cause:
No mapping was found for the run-as role in weblogic.xml.

Action:
Since the server has decided to use the implicit map, ensure that this is the principal-name you intended to use. The run-as role can be mapped to a principal name in weblogic.xml using either the run-as-role-assignment element or the servlet-descriptor/run-as-principal-name.

BEA-101303
Web application: {0}, the {1} role: {2} defined in the descriptor: {3} has not been mapped to a principal name in weblogic.xml. Also there is no security-role-assignment defined for this role. Will use the rolename itself as a principal-name for {1} for the servlet. The run-as role can be mapped to a principal name in weblogic.xml using either the run-as-role-assignment element or the servlet-descriptor/run-as-principal-name.

Category:
HTTP

Cause:
No mapping was found for the run-as role in weblogic.xml.

Action:
Since the server has decided to use the implicit map, ensure that this is the principal-name you intended to use. The run-as role can be mapped to a principal name in weblogic.xml using either the run-as-role-assignment element or the servlet-descriptor/run-as-principal-name.

BEA-101304
Web application: {0}, the {1}: {3} defined in web.xml {2} not been mapped to principals in security-role-assignment in weblogic.xml. Will use the rolename itself as the principal-name.

Category:
HTTP

Cause:
Did not find a mapping for the roles which were supposed to be mapped to a principal in security-role-assignment in weblogic.xml.

Action:
Since the server has decided to use the implicit map, ensure that this is the principal-name you intended to use.

BEA-101305
[{0}] Error-page location: "{1}" for the error code: "{2,number}" causes an infinite loop condition as it throws the same code for which it has been mapped.

Category:
HTTP

Cause:
The servlet for the error-page, which maps to the given error code, throws the same error code. This causes an infinite loop condition.

Action:
Fix the error page.

BEA-101306
Could not resolve entity "{0}" for the webapp at: "{1}". Check the DTD reference in the corresponding descriptor (web.xml/weblogic.xml).

Category:
HTTP

Cause:
The descriptor validation failed.

Action:
Check the DTD and ensure that the descriptors comply with that. Check the exception message for more details. Also, ensure that there are no typos in the DOCTYPE header.

BEA-101307
Got an error while resolving entity "{0}" for the Web application at: "{1}". Check the DTD reference in the corresponding descriptor (web.xml/weblogic.xml).

Category:
HTTP

Cause:
The descriptor validation failed.

Action:
Check the DTD and ensure that the descriptors comply with that. Check the exception message for more details. Also, ensure that there are no typos in the DOCTYPE header.

BEA-101310
Web server: {0}, failed to perform batched update for replicated sessions against jndiname: {1} on the secondary server: {2} http-port: {3} https-port: {4}

Category:
HTTP

Cause:
The Remote Management Interface (RMI) call from the trigger, which was intended to periodically update the read-only replicated sessions on the secondary server, failed.

Action:
Check the exception for the exact cause.

BEA-101317
The Web application: {0} has specified DIGEST as the auth-method in web.xml, which is not implemented. Will default to BASIC.

Category:
HTTP

Cause:
DIGEST authentication is not yet implemented. The Web application will fallback to BASIC authentication.

Action:
Choose either BASIC, FORM, or CLIENT-CERT.

BEA-101318
The Web application: {0} has specified: {1} as the auth-method in web.xml, which is not valid. Valid values are BASIC (default), FORM, and CLIENT-CERT.

Category:
HTTP

Cause:
An invalid authentication method was specified in web.xml.

Action:
The valid values are BASIC, FORM, and CLIENT-CERT. Fix the web.xml file for the Web application.

BEA-101319
The Web application: {0} has "FORM" based authentication specified but the mandatory element: {1} is left blank.

Category:
HTTP

Cause:
The form-login-page and form-error-page are mandatory elements when auth-method is "FORM."

Action:
Fix the web.xml for the specified Web application.

BEA-101325
The local-path: {1} specified for the virtual-directory-mapping specified in weblogic.xml for the Web application: {0} (docroot={2}), is not valid.

Category:
HTTP

Cause:
A relative path was possibly assigned to the local-path. If so, the container makes the path relative to the document root.

Action:
Ensure that the relative path exists with respect to the document root.

BEA-101326
The element: {1} contains an undefined security-role: {0}

Category:
HTTP

Cause:
The security-role definition is mandatory.

Action:
Ensure that the security role-name is defined in web.xml. Also check the DTD and examples for the correct syntax.

BEA-101327
The element: {0} is not allowed to appear more than once in the descriptor: {1}

Category:
HTTP

Cause:
The parser found more than one occurrence for the element.

Action:
Ensure that than the element appears only once (check the schema).

BEA-101328
{0}: invalid dispatcher: {2} for filter-mapping: {1}

Category:
HTTP

Cause:
An invalid value was found for the filter mapping dispatcher.

Action:
Valid values are: "REQUEST," "FORWARD," "INCLUDE," or "ERROR."

BEA-101331
Cannot deploy {0} from {1} on {2}, because there is already a non-versioned Web application named {3} loaded from {4}, using the context path {5}.

Category:
HTTP

Cause:
The Web application version that is being deployed has been assigned a context path that is already in use by a non-versioned Web application.

Action:
Choose a different context path or undeploy the conflicting Web application.

BEA-101332
Failed to register JACC policy context handlers for the Web application container.

Category:
HTTP

Cause:
This is an unexpected error.

Action:
See the error message for more information.

BEA-101337
Received a SecurityException during: {0}, for : {1}, Web application: {2}

Category:
HTTP

Cause:
The user does not have enough privileges.

Action:
See the error message for more information.

BEA-101338
The context parameter "weblogic.httpd.defaultServlet" has been deprecated. Instead, use the servletMapping = "/" to define the default servlet.

Category:
HTTP

Cause:
A deprecated context parameter was used.

Action:
The servlet weblogic.servlet.FileServlet is the default servlet. If you want to override the default, define a new servlet-mapping in web.xml with url-pattern = "/".

BEA-101339
The context parameter: {0} has been deprecated. Instead, use the element: {1} in weblogic.xml.

Category:
HTTP

Cause:
A deprecated context parameter was used.

Action:
Replace it with the suggested alternative in weblogic.xml.

BEA-101340
The context parameter "weblogic.httpd.servlet.classpath" has been deprecated. Instead use manifest classpath or WEB-INF/lib or WEB-INF/classes or virtual-directories in weblogic.xml

Category:
HTTP

Cause:
A deprecated context parameter was used.

Action:
There are better ways to extend the classpath exposed to the Web application classloader, including virtual-directories and a manifest classpath.

BEA-101341
{0}: Class file up-to-date for JSP: {1}

Category:
HTTP

Cause:
This message indicates that the class file associated with the JSP is up-to-date.

Action:
No action is required.

BEA-101342
{0}: Error(s) encountered while precompiling JSP {1} {2}

Category:
HTTP

Cause:
The JSP file shown by the error message had errors and could not be precompiled.

Action:
Correct the errors shown by the message so that it gets precompiled without errors.

BEA-101343
{0}: Attempting to precompile {1}, since the class file associated with it was found to be out-of-date.

Category:
HTTP

Cause:
This message indicates that the class file associated with the given JSP was out of date and needs recompilation.

Action:
No action is required.

BEA-101344
{0}: Attempting to precompile {1}, since the class file associated with it was not found in the Web application classpath.

Category:
HTTP

Cause:
This message indicates that the class file associated with the given JSP was not found in the Web application classpath and thus needs to be compiled.

Action:
No action is required.

BEA-101345
A change in value was detected for the "Fields" directive in access.log for webserver: {0}. Rotating the access.log. The value defined for the WebServerMBean will take precedence. Default being "time cs-method cs-uri sc-status". Old value: "{1}" and new value: "{2}".

Category:
HTTP

Cause:
This message indicates that the value from WebServerMBean.getELFFields() was different that the value in the "Fields" directive on the top of access.log.

Action:
Changing the ELF fields by hand editing access.log is no longer supported. Change the access.log "Fields" using the Administration Console.

BEA-101346
The virtual host name: {0} being used by the Virtual Host: {1} is already in use by: {2}

Category:
HTTP

Cause:
There is duplicate name usage for VirtualHostNames.

Action:
Fix the VirtualHostNames fields for the Virtual Host and choose a unique name.

BEA-101347
The server channel name (NetworkAccessPoint): {0} being used by the Virtual Host: {1} is already in use by: {2}

Category:
HTTP

Cause:
There is uplicate name usage for ServerChannelName for Virtual Hosts.

Action:
Fix the ServerChannelName field for the Virtual Host and choose a unique name.

BEA-101348
The server channel name (NetworkAccessPoint): {0} being used by the Virtual Host: {1} is not defined. This virtual host will not be deployed.

Category:
HTTP

Cause:
The NetworkAccessPoint is not yet defined.

Action:
Choose a different NetworkAccessPoint name or define a new one using the Administration Console.

BEA-101349
Failed to save the WorkContexts into the session or cache for the request: {0}

Category:
HTTP

Cause:
An unexpected exception occurred.

Action:
At the end of the request, the Web application container saves the WorkContexts into the session and the local cache in order to propagate them between successive HTTP requests. Contact My Oracle Support and report this problem.

BEA-101350
Web application(s) {2} of module {1} of application {0} has {3} pending session(s) respectively.

Category:
HTTP

Cause:
The server has detected pending sessions for the Web application module while the application is gracefully transitioning from running to administration mode.

Action:
No action is required. Use the -force option to ignore inflight work and bring the application to administration mode.

BEA-101351
Server has detected pending sessions while gracefully transitioning webapp module {1} of application {0} from running to administration mode. Server will wait for pending sessions to either become invalidated or timed out. The current timeout value is {2} seconds. To terminate sessions immediately, use the -force option.

Category:
HTTP

Cause:
During graceful transition of the application from running to administration mode, the server waits for inflight work to complete. This includes pending sessions.

Action:
No action is required. Use the -force to ignore inflight work and force transition of the application from running to administration mode.

BEA-101352
There are no active sessions. The Web application module {1} of application {0} is ready to go into administration mode.

Category:
HTTP

Cause:
All active sessions have completed. The Web service is ready to gracefully transition to administration mode.

Action:
No action is required.

BEA-101354
Web application(s) {3} of module {1} of application {0} still have pending sessions after {2} minutes of initiating transition from running to administration mode. Waiting for pending sessions to finish.

Category:
HTTP

Cause:
The server is waiting for the application sessions to finish before gracefully shutting down.

Action:
No action is required. Use the -force option to ignore inflight work and force transition of the application into administration mode.

BEA-101355
[{0}] Version {2} is specified for Web Services {1}, but versioning of Web Services is not supported.

Category:
HTTP

Cause:
An attempt was made to deploy Web Services with versioning.

Action:
Deploy the Web Services (or the application containing the Web Services) without versioning.

BEA-101356
Web application: {0} failed to load the shared library (fastfile) for using native I/O in the FileServlet, falling back to the standard I/O.

Category:
HTTP

Cause:
An unexpected error occurred while attempting to load the native library (fastfile) for using native I/O in the FileServlet.

Action:
Ensure that the shared library (fastfile) exists in a directory that is in the LD_LIBRARY_PATH or PATH. Also, note that native I/O is supported on Windows, Linux, and Solaris. If problem persists, contact My Oracle Support.

BEA-101357
A force graceful production to administration mode transition was initiated. The Web application module {1} of application {0} is ready to go into administration mode.

Category:
HTTP

Cause:
A force graceful production to administration mode transition was initiated. The Web service is ready to transition to administration mode.

Action:
No action is required.

BEA-101359
The servlet {0} initilization method failed while it was run in the background. The exception was: {1}.

Category:
HTTP

Cause:
The servlet initilization method caused an exception.

Action:
The cause of the exception must be corrected and then the application should be redeployed.

BEA-101360
Recompiling JSP [{0}], resource [{1}], because it is stale.

Category:
HTTP

Cause:
The JSP was changed from the last time it was compiled.

Action:
The JSP will be always recompiled if it is different from the last compiled version.

BEA-101361
[{0}] A library reference in weblogic.xml has an illegal Specification-Version: {1}. The Specification-Version must be a valid version string: int(.int)*, int >=0. For example: 2.1.1.

Category:
HTTP

Cause:
The Specification-Version of a library reference in weblogic.xml cannot be parsed.

Action:
Fix the library's Specification-Version in weblogic.xml to conform to the required version string syntax.

BEA-101362
[{0}] could not deserialize the {1} scoped attribute with name: "{2}"

Category:
HTTP

Cause:
Classloader changed. When this happens, the old attributes will be deserialized using the new classloader. The classloader can change either as the result of a dynamic reload of classes (controlled by weblogic.xml parameter "reload-check-secs" or upon across webapp dispatch (include or forward).

Action:
Ensure that the attribute class is available to the Web application scope and that the attribute class and all the references it holds are serializable.

BEA-101363
Application: {0}, Web application: {1} has context-root specified in application.xml: "{2}". The context-root specified in weblogic.xml: "{3}" will be ignored.

Category:
HTTP

Cause:
The context-root specified in application.xml takes higher precedence than the one in weblogic.xml.

Action:
This is an informational message. Ensure that this is what you intended to do.

BEA-101364
{0}:{1} Failure while precompiling JSP: {2}.

Category:
HTTP

Cause:
The JSP failed to precompile on a partial update.

Action:
Check the exception for the exact cause.

BEA-101366
The server could not send the HTTP message during the configured timeout value. The socket has been closed.

Category:
HTTP

Cause:
This is an informational message.

Action:
Bump up the value of CompleteMessageTimeout. The default is 60 seconds. If you have slow clients that cannot complete the messsage transfer and are getting timed out, raise the value.

BEA-101367
An error occurred while extracting archived file for "{0}", located at "{1}".

Category:
HTTP

Cause:
An error occurred while extracting the archived WAR file, due to path length limitations on some OS's.

Action:
Some OS's only allow a certain number of characters in the file name. This limitation can be noticed when extracting an archive in a deeply nested directory. Since the default temporary directory for extracting all archives is relative to the server root directory, it is recommended that one use the system property weblogic.j2ee.application.tmpDir and set it to a shorter file path, or one could ensure that the server is started in a directory with a shorted file path.

BEA-101369
{0}: The encoding jsp-descriptor parameter has been deprecated. Consider declaring the encoding in the jsp-config element (web.xml) or as a page directive (pageEncoding) instead.

Category:
HTTP

Cause:
{0}: The encoding jsp-descriptor parameter has been deprecated.

Action:
Consider declaring the encoding in the jsp-config element (web.xml) or as a page directive (pageEncoding) instead.

BEA-101370
There was a failure when merging library descriptors into the application descriptors for application {0}. Ensure that the descriptors are valid. The error is {1}

Category:
HTTP

Cause:
The library or the application descriptors are invalid.

Action:
Fix the descriptors in the application or the library.

BEA-101371
There was a failure when processing annotations for application {0}. Ensure that the annotations are valid. The error is {1}

Category:
HTTP

Cause:
The descriptor has an invalid servlet-class, filter-class, or listener-class.

Action:
Fix the descriptors in the application or the library.

BEA-101372
There was a failure in application {0} when attempting to inject dependencies into {1}. Dependencies will not be injected into this class.

Category:
HTTP

Cause:
The annotations defined in the class may be invalid or the descriptor may have conflicting entries.

Action:
Check the annotations defined in this class. Also, verify that the descriptor has valid entries.

BEA-101373
Reloading classes in application {0} failed due to change of annotations on a refreshed class. Modified or new annotations will not be processed during servlet reload as they involve a non-dynamic change. Redeploy the application for these annotations to be processed.

Category:
HTTP

Cause:
New or modified annotations will not be processed in application {0} due to a servlet refresh.

Action:
Redeploy the application for reloading classes when annotations are modified.

BEA-101374
The Web container failed to look up the transaction associated with the current thread for Web application: ${0}.

Category:
HTTP

Cause:
After the response is sent, the container needs to check if there is any active transaction associated with the thread so that it can abort the transaction. See the exception message for more details.

Action:
See the exception message for more details.

BEA-101375
[{0}]: Error while parsing the JSF Configuration Descriptor at "{1}".

Category:
HTTP

Cause:
A JSF Configuration Descriptor parsing exception occurred.

Action:
Check the exception for the exact cause.

BEA-101376
Unable to purge cache of Bean classes from BeanELResolver, error occurs at "{0}".

Category:
HTTP

Cause:
Unable to get the cache property of BeanELResolver.

Action:
Contact My Oracle Support and report this problem.

BEA-101377
Filtering class loader configuration ignored for web module {1} of application {0}.

Category:
HTTP

Cause:
Filtering class loader configuration is only supported in descriptors at the main level of the deployment (for example, in enterprise applications or standalone web applications). This configuration is not supported in Web modules of an enteprise application.

Action:
Remove the filtering class loader configuration from the deployment descriptor of web module {1} of application {0}.

BEA-101378
The version of OpenJPA shipped with WebLogic Server does not support JPA 2.0. Recompile the application with the JPA 1.0 API JAR available at http://www.jcp.org/en/jsr/summary?id=220.

Category:
HTTP

Cause:
The Kodo-OpenJPA persistence provider that ships with WebLogic Server does not support JPA 2.0.

Action:
Recompile the application with the JPA 1.0 API jar available at http://www.jcp.org/en/jsr/summary?id=220 or use TopLink if you wish to use a JPA 2.0 persistence provider.

BEA-101379
Starting with WebLogic Server 10.3.4.0, some methods changed in the OpenJPA interfaces that ship with WebLogic Server. Recompile the application with the OpenJPA JAR in your WebLogic Server installation.

Category:
HTTP

Cause:
Some methods in the OpenJPA interfaces that ship with WebLogic Server have changed.

Action:
Recompile the application with the OpenJPA JAR in your WebLogic Server installation.

BEA-101380
There is more than one Web fragment with the same name: "{0}".

Category:
HTTP

Cause:
There is more than one Web fragment with the same name.

Action:
Change the duplicate Web fragment names to avoid the conflict.

BEA-101381
Both before others and after others found in Web fragment: "{0}".

Category:
HTTP

Cause:
Both before others and after others was found in the Web fragment.

Action:
Ensure that the Others element appears only in before or after.

BEA-101382
WLServlet annotation cannot be used with WebServlet together.

Category:
HTTP

Cause:
WLServlet annotation cannot be used with WebServlet together.

Action:
Oracle recommends that you use only servlet 3.0 annotations.

BEA-101383
WLFilter annotation can't be used with WebFilter together

Category:
HTTP

Cause:
WLFilter annotation can't be used with WebFilter together.

Action:
Suggest to use servlet 3.0 annotations only

BEA-101384
{0} annotation is deprecated, please use servlet 3.0 annotation instead. App:{1}, Class:{2}

Category:
HTTP

Cause:
The older WL annotations are deprecated, and replaced by servlet 3.0 annotations, for example WLServlet is replaced by WebServlet, WLFilter is replaced by WebFilter.

Action:
Suggest to use servlet 3.0 annotations instead if WL annotations

BEA-101385
WebListener annotation is used illegally, the class annotated by WebListener must implement listener interface

Category:
HTTP

Cause:
WebListener annotation is used illegally, the class annotated by WebListener must implement listener interface, for example: javax.servlet.ServletContextListener and so on, please check the servlet 3.0 specification.

Action:
The class annotated by WebListener must implement listener interface, for example: javax.servlet.ServletContextListener and so on, suggest to check the servlet 3.0 specification.

BEA-101386
The ServletSecurity Annotation is illegal, the root is {0}

Category:
HTTP

Cause:
The ServletSecurity Annotation is illegal, the root is {0}.

Action:
Suggest not to correct ServletSecurity Annotation accroding to the Servlet 3.0 Specification.

BEA-101387
ServletContext has already been initialized, cannot call method {0} any longer.

Category:
HTTP

Cause:
ServletContext has already been initialized, cannot call method {0} any longer.

Action:
Check Servlet 3.0 Specification and the corresponding javadoc.

BEA-101388
The ServletContext was passed to the ServletContextListener.contextInitialized method of a ServletContextListener that was neither declared in web.xml or web-fragment.xml, nor annotated with javax.servlet.annotation.WebListener.

Category:
HTTP

Cause:
The ServletContext was passed to the ServletContextListener.contextInitialized method of a ServletContextListener that was neither declared in web.xml or web-fragment.xml, nor annotated with javax.servlet.annotation.WebListener.

Action:
Check Servlet 3.0 Specification and the corresponding javadoc.

BEA-101389
Cannot add this ServletContextListener

Category:
HTTP

Cause:
Because this ServletContext was passed to the ServletContextListener's contextInitialized() method of a ServletContextListener that was neither declared in web.xml or web-fragment.xml, nor annotated with javax.servlet.annotation.WebListener.

Action:
Check Servlet 3.0 Specification and the corresponding javadoc.

BEA-101390
It is illegal to use both value and urlPatterns attributes together in the same WebServlet/WebFilter annotation: {0}.

Category:
HTTP

Cause:
As per the Servlet 3.0 specification, section 8.1, both the value attribute and urlPatterns attribute were detected in the identical WebServlet/WebFilter annotation.

Action:
Use either the value attribute or urlPatterns attribute, but not both at the same time in the same annotation.

BEA-101391
Circular references found in web fragments relative ordering.

Category:
HTTP

Cause:
Circular references found in web fragments relative ordering.

Action:
Use absolute ordering to overwrite relative ordering or change relative ordering config.

BEA-101392
Glassfish Descriptor element <{0}> was successfully parsed and applied.

Category:
HTTP

Cause:
This is an information message.

Action:
No action is required if the element parsing was successful.

BEA-101393
Glassfish Descriptor element <{0}> is not supported by WebLogic.

Category:
HTTP

Cause:
This is an informational message.

Action:
No action is required. Note that the element is ignored by the descriptor parser.

BEA-101394
The exception "{0}" occurred when processing getParameter or getParameterValues from a multipart value of a ServletRequest.

Category:
HTTP

Cause:
The exception "{0}" occurred when processing getPart or getParts from a ServletRequest.

Action:
Check whether the size of the uploaded file exceeds the size limit. Check that the content of the post-multipart form data is correct.

BEA-101395
Application or module {0} is deployed as a web application.

Category:
HTTP

Cause:
The spplication or module {0} was deployed as a web application because there was no hint (descriptors or classes annotated by component annotations) detected. WebLogic Server deploys applications without deployment descriptors or classes annotated by component annotations as web application.

Action:
No action is required if the application is a web application or a web module. Otherwise, add the corresponding deployment descriptors so that WebLogic Server can detect the application type correctly.

BEA-101396
Either the urlPatterns or the value attribute in the WebServlet annotation MUST be present: {0}.

Category:
HTTP

Cause:
As per the Servlet 3.0 specification, section 8.1.1, neither the value attribute nor the urlPatterns attribute was detected in the WebServlet annotation.

Action:
Use either the value attribute or urlPatterns attribute, but not both at a same time in the same annotation.

BEA-101397
The urlPatterns attribute, servletNames attribute, or value attribute of the WebFilter annotation MUST be specified: {0}.

Category:
HTTP

Cause:
As per the Servlet 3.0 specification, section 8.1.2, neither the urlPatterns attribute, servletNames attribute, nor value attribute was detected in the WebFilter annotation.

Action:
Use either the urlPatterns, servletNames, or value attribute in the annotation. Do not use both the urlPatterns and value attributes at a same time in the same annotation.

BEA-101398
Exception : [{0}][{1}] during request upgrade.

Category:
HTTP

Cause:
An error occurred while creating an instance of HttpUpgradeHandler. [{0}][{1}]

Action:
Check whether the Implement of HttpUpgradeHandler exists or the class has been put under the correct classpath.

BEA-101399
The Web application: {0} has specified DIGEST as the auth-method in web.xml, which is not implemented.

Category:
HTTP

Cause:
DIGEST authentication is not yet implemented.

Action:
Choose either BASIC, FORM, or CLIENT-CERT.

BEA-101400
The value of {0} attribute {1} can not be serialized and will be removed when reloading the application, the class of the value object is {2}.

Category:
HTTP

Cause:
An exception occurred when serializing the attribute value.

Action:
Either correct the serialization issue of the attribute value class or ignore this warning if it is harmless for application reloading.

BEA-101401
The url-pattern {0} in web application {1} is mapped to multiple Servlets.

Category:
HTTP

Cause:
The effective web.xml, after merging information from fragments and annotations, contains url-patterns that are mapped to multiple servlets.

Action:
Check the web.xml, fragment.xml, and annotations to remove the multiple url-patterns mapping issue of the servlets.

BEA-101402
Cannot get Request or Response when the current state is completed or dispatched.

Category:
HTTP

Cause:
Try to get Request or Response from a completed or dispatched AsyncContext.

Action:
Try to call AsyncContext.getRequest and AsyncContext.getResponse after the asynchronous request is completed or dispatched.

BEA-101403
For security constraint with url-pattern {0} in web application {1}, only the http methods "{2}" are covered.

Category:
HTTP

Cause:
During application deployment, the container must inform the deployer of any uncovered http methods that are present in the application security constraint configuration resulting from the combination of the constraints defined for the application.

Action:
Check the security constraint in the web application. Remove the uncovered http methods.

BEA-101404
For security constraint with url-pattern {0} in web application {1}, the http methods "{2}" are uncovered.

Category:
HTTP

Cause:
During application deployment, the container must inform the deployer of any uncovered HTTP methods that are present in the application security constraint configuration resulting from the combination of the constraints defined for the application.

Action:
Check the security constraint in the web application. Remove the uncovered http omitted methods.

BEA-101405
The preliminary servlet {0} defined in web.xml or web-fragment.xml has not been completed through the ServletContext.addServlet() API by any ServletContextListener or ServletContainerInitializer.

Category:
HTTP

Cause:
The servlet does not have any servlet-class or jsp-file configured in web.xml or web-fragment.xml. Therefore it does not get completed by by ServletContextListener or ServletContainerInitializer with the programmatically servlet adding API of ServletContext.

Action:
Ensure that the servlet is completed in web.xml or web-fragment.xml, or can be completed by ServletContextListener or ServletContainerInitializer with the programmatically servlet adding API of ServletContext.

BEA-101406
Filter Name cannot be a Null or Empty string.

Category:
HTTP

Cause:
The filter name is a Null or Empty string when calling ServletContext.addFilter().

Action:
Check the application. Add a 'not null' string type name for ServletContext.addFilter().

BEA-101407
Servlet Name cannot be a Null or Empty string.

Category:
HTTP

Cause:
The Servlet name is a Null or Empty string when calling ServletContext.addServlet().

Action:
Check the application. Add a 'not null' string type name for ServletContext.addServlet().

BEA-101408
[{0}] An error occurred while removing WLDFDataAccessRuntimeMBean.

Category:
HTTP

Cause:
The WLDFDataAccessRuntimeMBean associated with Web application {0} could not be removed.

Action:
Check the exception for the exact error message.

BEA-101409
The referenced shared library {0} {1} will be ignored and the {0} library in system class path will be used.

Category:
HTTP

Cause:
Since WebLogic Server 12c, application is unnecessary to reference shared library to use JSF/JSTL feature. Since WebLogic Server 12.2.1, the referenced JSTL 1.2 and JSF 2.x shared library in application will be ignored. The JSF/JSTL shared library in system classpath will be used.

Action:
The JSF 2.x/JSTL 1.2 library-ref in deployment descriptor should be removed.

BEA-101410
Secure mode is enabled in WLS domain, the servlet {0} uses weblogic.servlet.ServletServlet which should not be used in WLS secure mode.

Category:
HTTP

Cause:
The servlet weblogic.servlet.ServletServlet is recommended to be not used in WLS secure mode.

Action:
Please remove weblogic.servlet.ServletServlet and existing mappings in web.xml of your application. Please refer to document *Oracle® Fusion Middleware Securing a Production Environment for Oracle WebLogic Server*, Chapter 3 "Ensuring the Security of Your Production Environment" for more details.

BEA-101411
There's IOException thrown when web application [{0}] sends error response to client. The IOException is {1}

Category:
HTTP

Cause:
An unexpected IOException was thrown when sending error message to client.

Action:
Check the exception for the exact cause of the problem.

BEA-110000
Transaction log record class name encoding error [{0}]: {1}

Category:
JTA

Cause:
An error occurred while writing a record to the transaction log.

Action:
Check for other log messages that give more information about the failure.

BEA-110001
Transaction log record encoding error [{0}]: {1}

Category:
JTA

Cause:
An error occurred while writing a record to the transaction log. See the reported exception for more details.

Action:
Check for other log messages that give more information about the failure.

BEA-110003
onError() callback exception: {0}

Category:
JTA

Cause:
An error occurred while writing a record to the transaction log.

Action:
Check for other log messages that give more information about the failure.

BEA-110004
Unable to read transaction log record checksum.

Category:
JTA

Cause:
The transaction log file is corrupted, possibly due to a crash or file system error. If this error occurs only once per system reboot, a crash caused the transaction being logged at that time to be rolled back.

Action:
No action is required. Recovery is automatic.

BEA-110005
Transaction log record checksum failure [{0}].

Category:
JTA

Cause:
A record in the transaction log file is corrupted, possibly due to a crash or file system error. If this error occurs only once per system re-boot, a crash caused the transaction being logged at that time to be rolled back.

Action:
No action is required. Recovery is automatic.

BEA-110007
Log record class instantiation problem [{0}]: {1}

Category:
JTA

Cause:
An error occurred while reading a record from the transaction log. This may have also occurred due to crash recovery processing of a new transaction log file performed by an older WebLogic Server software version.

Action:
Check for other log messages that give more information about the failure.

BEA-110008
Log record class readExternal problem [{0}]: {1}

Category:
JTA

Cause:
An error occurred while reading externalized state information for a record from the transaction log. This may have also occurred due to crash recovery processing of a new transaction log file performed by an older WebLogic Server software version.

Action:
Check for other log messages that give more information about the failure.

BEA-110011
onRecovery() callback exception: {0}.

Category:
JTA

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-110013
An error occurred while writing transaction log: {0}.

Category:
JTA

Cause:
The file system is full or permission problems exist.

Action:
Verify the transaction log file location and locate any file system problems.

BEA-110015
A version error occurred while reading the transaction log header file.

Category:
JTA

Cause:
File corruption exists. A new transaction log file may have been given to an older version of WebLogic Server.

Action:
The system will automatically create an empty transaction log.

BEA-110020
Error reading transaction log file [{0}]: {1}

Category:
JTA

Cause:
There are file system or permission problems, or possible corruption of the transaction log.

Action:
Verify the transaction log file location and check for file system problems. Crash recovery processing continues as best it can.

BEA-110021
Format error [{0}] occurred while reading transaction log file [{1}]

Category:
JTA

Cause:
The transaction log file was possibly corrupted.

Action:
Contact My Oracle Support.

BEA-110022
Format error [{0}] occurred while reading transaction log file [{1}]: {2}

Category:
JTA

Cause:
The transaction log file is possibly corrupted.

Action:
Contact My Oracle Support.

BEA-110023
Transaction log record checksum failure [{0}]: {1}.

Category:
JTA

Cause:
A record in the transaction log file is corrupted, possibly due to a crash or file system error. If this error occurs only once per system reboot, a crash caused the transaction being logged at that time to be rolled back.

Action:
No action is required. Recovery is automatic.

BEA-110026
Missing transaction log file [{0}]

Category:
JTA

Cause:
File system or permission problems exist, or the transaction log might be corrupted. The file might also have been manually deleted.

Action:
Verify the transaction log file location and check for file system problems. Crash recovery processing will continue.

BEA-110028
The transaction manager did not call XA.forget() for transaction [{1}] on resource [{0}], which reported a heuristic decision during commit.

Category:
JTA

Cause:
See the message details for probable cause.

Action:
After correcting any data inconsistencies due to the heuristic outcome, use the resource manager administrative commands to instruct the resource to ignore the transaction.

BEA-110029
The transaction manager did not call XA.forget() for transaction [{1}] on resource [{0}], which reported a heuristic decision during rollback.

Category:
JTA

Cause:
See the message details for the probable cause.

Action:
After correcting any data inconsistencies due to the heuristic outcome, use the resource manager administrative commands to instruct the resource to ignore the transaction.

BEA-110030
XA resource [{0}] has not responded in the last {1} second(s).

Category:
JTA

Cause:
The resource is unavailable (possibly the resource is down, or network problems exist).

Action:
Check the resource manager and network condition. When the resource is available again, take the following actions to inform the Transaction Manager: For JDBC connection pools, refresh the connection pool. You can also enable the auto-refresh feature of the connection pool to do this automatically. For other third-party XA resources, the resource provider should re-register the resource by calling weblogic.transaction.TransactionManager.unregisterResource(), followed by weblogic.transaction.TransactionManager.registerStaticResource() or weblogic.transaction.TransactionManager.registerDynamicResource().

BEA-110033
Recovered transaction log header file from backup location [{0}].

Category:
JTA

Cause:
This error is probably caused by a crash that occurred when the the transaction log header file was being rewritten.

Action:
No action is required. Recovery is automatic.

BEA-110101
No license exists for two-phase commit (2PC) processing.

Category:
JTA

Cause:
The 2PC license is not present.

Action:
Contact an Oracle sales representative to obtain a 2PC license.

BEA-110102
A transaction with multiple resources was rolled back due to an invalid two-phase commit (2PC) license.

Category:
JTA

Cause:
The 2PC license is not present.

Action:
Contact an Oracle sales representative to obtain a 2PC license.

BEA-110200
User [{0}] is not authorized to invoke startCommit on a transaction branch.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternately, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-110201
User [{0}] is not authorized to invoke startRollback on a transaction branch.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that client software is not directly invoking an internal WebLogic system object.

BEA-110202
User [{0}] is not authorized to invoke rollback on a transaction branch.

Category:
JTA

Cause:
This might be a symptom of a potential security attack, or alternately, a problem with the "system" security identity of the server.

Action:
Verify that client software is not directly invoking an internal WebLogic system object.

BEA-110204
XA resource [{0}] returns XAER_RMFAIL and is unavailable.

Category:
JTA

Cause:
The resource is unavailable because is down or network problems exist.

Action:
Check the resource manager and network conditions. When the resource is available again, take the following actions to inform the Transaction Manager: For JDBC connection pools, refresh the connection pool. You can also enable the auto-refresh feature of the connection pool to do this automatically. For other third-party XA resources, the resource provider should re-register the resource by calling weblogic.transaction.TransactionManager.unregisterResource(), followed by weblogic.transaction.TransactionManager.registerStaticResource() or weblogic.transaction.TransactionManager.registerDynamicResource().

BEA-110207
A previously unavailable XA resource [{0}] is now available.

Category:
JTA

Cause:
The previously unavailable resource is now available. It is possible that the resource has recovered from earlier failures or that previous network problems were cleared.

Action:
No action is required.

BEA-110208
Unregistration of Transaction Recovery Service for server [{0}] failed.

Category:
JTA

Cause:
An attempt to unregister the Transaction Recovery Service for server [{0}] from the migratable service framework failed.

Action:
Check for other log messages that give more information about the failure.

BEA-110209
Registration of Transaction Recovery Service for server [{0}] failed.

Category:
JTA

Cause:
An attempt to register the Transaction Recovery Service for server [{0}] from the migratable service framework failed.

Action:
Check for other log messages that give more information about the failure.

BEA-110210
Failback of Transaction Recovery Service for server [{0}] failed.

Category:
JTA

Cause:
Transaction recovery actions are performed for the Transaction Recovery Service for server [{0}]. An attempt to failback the Transaction Recovery Service failed.

Action:
Examine the migration errors and perform manual migration of the Transaction Recovery Service back to server [{0}].

BEA-110211
Failback retry of Transaction Recovery Service for server [{0}] failed.

Category:
JTA

Cause:
Transaction recovery actions are performed for the Transaction Recovery Service for server [{0}]. Both the first and second attempt to failback the Transaction Recovery Service failed. JTA is going to give up implicitly failing back the Transaction Recovery Service for server [{0}].

Action:
Examine the migration errors and perform manual migration of the Transaction Recovery Service back to server [{0}].

BEA-110212
An attempt was made to manually migrate the Transaction Recovery Service of the current server away from the server while it is still active.

Category:
JTA

Cause:
An attempt was made to manually migrate the current Transaction Recovery Service away from the server while it is still active.

Action:
For controlled migration, suspend or shut down the current server first before manually migrating it to a backup server.

BEA-110213
The activation of Transaction Recovery Service for server [{0}] failed.

Category:
JTA

Cause:
The activation of Transaction Recovery Service for server [{0}] failed.

Action:
Examine the error details, correct the error conditions, and perform the necessary manual migration again if possible. If unsuccessful, My Oracle Support.

BEA-110400
An error occurred while unregistering Resource Runtime MBean: {0}

Category:
JTA

Cause:
The MBean may have been unregistered previously or there may be an issue with the JMX Administration Server.

Action:
No action is required.

BEA-110401
Ignoring error in afterCompletion. Object={0}, Exception={1}

Category:
JTA

Cause:
The application-defined javax.transaction.Synchronization callback may have caused an exception.

Action:
No action is required.

BEA-110402
Unknown state in getStatus(): {0}.

Category:
JTA

Cause:
The Transaction.getStatus() method was called and the transaction status is not a valid value.

Action:
Check for other log messages that give more information about the failure.

BEA-110403
An unexpected exception occurred while processing a transaction during a transaction manager timer event. Exception={0}.

Category:
JTA

Cause:
Refer to the exception information found in the error message.

Action:
No action is required.

BEA-110405
Resource {0} was not assigned to any of these servers: {1}

Category:
JTA

Cause:
The transaction coordinator maintains information regarding where resources are registered among all the servers that are known to the coordinator. The participating resource may have been unregistered or became unavailable prior to attempting the operation. This condition may also occur if the cache belonging to the coordinator was out of date or has not completed initialization at the time the operation was invoked.

Action:
Verify the state of resource managers participating in the transaction and retry the operation.

BEA-110406
Internal error interpreting heuristic status. Expected={0}, Actual={1}

Category:
JTA

Cause:
The heuristic completion status of a transaction is calculated based on the expected and actual completion states of all participants. The logic to determine the heuristic outcome did not account for the combination of the actual and expected completion states.

Action:
Check for other log messages that give more information about the failure.

BEA-110407
Unknown state in getStatus(): {0}

Category:
JTA

Cause:
The Transaction.getStatus() method did not recognize the transaction state as a valid state.

Action:
Check for other log messages that give more information about the failure.

BEA-110408
An attempt to add a duplicate transaction to the transaction manager list was ignored.

Category:
JTA

Cause:
The internal transaction table of the server already contains the transaction instance being added. This event is innocuous.

Action:
Check for other log messages that give more information about the failure.

BEA-110409
Unable to advertise resource {0}: {1}

Category:
JTA

Cause:
A problem may exist with the JNDI provider, or another object is already bound to this context.

Action:
Contact My Oracle Support.

BEA-110410
Unable to create resource runtime MBean for resource {0}: {1}

Category:
JTA

Cause:
There may be a problem with the JMX Administration Server, or another MBean with this name is already registered with the Administration Server.

Action:
Contact My Oracle Support.

BEA-110411
Failed to construct local ServerCoordinatorDescriptor: {0}.

Category:
JTA

Cause:
During server initialization, information about the local server could not be obtained from the local JNDI context.

Action:
Check for other log messages that give more information about the failure.

BEA-110412
{0} completed heuristically: {1}.

Category:
JTA

Cause:
The resource manager may have failed, timed out, or detected locking conflicts that prompted it to commit or roll back work for the transaction branch. If the heuristic error was due to a resource manager failure, the resource may not be able to determine if work for the transaction branch was committed, aborted, or both. In this case, the condition is considered a HAZARD or MIXED heuristic.

Action:
Check the participants of the transaction should be checked for possible data corruption. The resource manager reporting the heuristic may maintain state information related to the updates involved in the heuristic error. If the JTA ForgetHeuristics configuration parameter is set to false, this information may be preserved in the resource manager. This information might be useful in correcting any data inconsistencies.

BEA-110414
Illegal State (expected: Prepared or Committing): {0}

Category:
JTA

Cause:
While attempting to retry the commit phase of a transaction, it was detected that the state of the transaction is not valid. To be in the commit phase, a transaction can only be in the prepared or committing states.

Action:
Check for other log messages that give more information about the failure.

BEA-110415
Illegal state. Proceeding with rollback anyway. {0}

Category:
JTA

Cause:
While attempting to retry the rollback of a prepared transaction, it was detected that the state of the transaction is not valid.

Action:
Check for other log messages that give more information about the failure.

BEA-110419
An attempt was made to add an incompatible object as a transaction property: keys must be strings and values must be serializable.

Category:
JTA

Cause:
An attempt was made to add an incompatible object as a transaction property (the class of the key object must be a string and the class of the value object must be serializable).

Action:
Change the application to assign the transaction property using a String key and a serializable value.

BEA-110420
An attempt was made to add an incompatible object as a local transaction property: keys must be String.

Category:
JTA

Cause:
An attempt was made to add an incompatible object as a local transaction property (the key object must be of the class String).

Action:
Change the application to add the local property with a String key.

BEA-110421
Timer method was called on committed transaction {0}.

Category:
JTA

Cause:
The transaction manager invoked a timer method on a transaction that has already completed. The transaction manager periodically checks for transactions that should be aborted due to timeout. This transaction should have been removed from the internal transaction table.

Action:
Check for other log messages that give more information about the failure. No action required.

BEA-110422
Forcibly aborting a transaction found in an unexpected internal state. Details={0}

Category:
JTA

Cause:
While processing a transaction, the transaction manager detected that the transaction is in an illegal state. The only course of action for the coordinator is to attempt to force a rollback of all participants.

Action:
Check for any data inconsistencies among participating resources. Contact My Oracle Support.

BEA-110423
Abandoning transaction after {0} seconds: {1}

Category:
JTA

Cause:
A resource or participating server may have been unavailable for the duration of the AbandonTimeoutSeconds period.

Action:
Check participating resources for heuristic completions and correct any data inconsistencies.

BEA-110424
An unexpected exception was caught during begin: {0}

Category:
JTA

Cause:
Check the exception detail portion of the log message.

Action:
Correct the condition described in the exception detail portion of the log message.

BEA-110425
Error advertising TransactionManager object: {0}

Category:
JTA

Cause:
There may be a problem with the JNDI provider or another object is already bound to this context.

Action:
Contact My Oracle Support.

BEA-110426
An error occurred while advertising UserTransaction object: {0}

Category:
JTA

Cause:
There may be a problem with the JNDI provider, or another object is already bound to this context.

Action:
Contact My Oracle Support.

BEA-110427
An error occurred while advertising Coordinator object: {0}

Category:
JTA

Cause:
There may be a problem with the JNDI provider, or another object is already bound to this context.

Action:
Contact My Oracle Support.

BEA-110428
An error occurred while exporting Coordinator object ID: {0}

Category:
JTA

Cause:
Another remote object may be bound to this object ID.

Action:
Contact My Oracle Support.

BEA-110429
Error advertising SubCoordinator object: {0}.

Category:
JTA

Cause:
There may be a problem with the JNDI provider, or another object is already bound to this context.

Action:
Contact My Oracle Support.

BEA-110433
Unable to obtain ownership of the transaction log.

Category:
JTA

Cause:
The Transaction Recovery Service associated with the current server is currently owned by other servers.

Action:
Migrate the Transaction Recovery Migratable Service back to the current server before restarting it.

BEA-110442
An administrative request was made to locally roll back the transaction associated with Xid {0}

Category:
JTA

Cause:
The forced local rollback operation was initiated by an administrative application.

Action:
No action is required.

BEA-110443
An administrative request was made to locally commit the transaction associated with Xid {0}

Category:
JTA

Cause:
The forced local commit operation was initiated by an administrative application.

Action:
No action is required.

BEA-110444
An administrative request was made to globally commit the transaction associated with Xid {0}.

Category:
JTA

Cause:
A forced global rollback operation was initiated by an administrative application.

Action:
No action is required.

BEA-110445
An administrative request was made to globally commit the transaction associated with Xid {0}.

Category:
JTA

Cause:
A forced global commit operation was initiated by an administrative application.

Action:
No action is required.

BEA-110446
The administrative request to locally roll back the transaction associated with Xid {0} failed because the transaction does not exist.

Category:
JTA

Cause:
The transaction may have completed before the administrative request was made.

Action:
No action is required.

BEA-110447
The administrative request to locally commit the transaction associated with Xid {0} failed because the transaction does not exist.

Category:
JTA

Cause:
The transaction may have completed before the administrative request was made.

Action:
No action is required.

BEA-110448
The administrative request to globally roll back the transaction associated with Xid {0} failed because the transaction does not exist.

Category:
JTA

Cause:
The transaction may have completed before the administrative request was made.

Action:
No action is required.

BEA-110449
The administrative request to globally commit the transaction associated with Xid {0} failed because the transaction does not exist

Category:
JTA

Cause:
The transaction may have completed before the administrative request was made.

Action:
No action is required.

BEA-110450
The administrative request to locally roll back the transaction {0} encountered an error {1}.

Category:
JTA

Cause:
Refer to the exception information in the error message.

Action:
Check to see if the transaction still exists. The operation may have resolved the transaction. If the problem persists, contact My Oracle Support.

BEA-110451
The administrative request to globally roll back the transaction {0} encountered an error {1}.

Category:
JTA

Cause:
Refer to the exception information in the error message.

Action:
Check to see if the transaction still exists; the operation may have resolved the transaction. If the problem persists, contact My Oracle Support.

BEA-110452
The administrative request to locally commit the transaction {0} encountered an error {1}.

Category:
JTA

Cause:
Refer to the exception information in the error message.

Action:
Check to see if the transaction still exists. The operation may have resolved the transaction. If the problem persists, contact My Oracle Support.

BEA-110453
The administrative request to globally commit the transaction {0} encountered an error {1}.

Category:
JTA

Cause:
Refer to the exception information in the error message.

Action:
Check to see if the transaction still exists. The operation may have resolved the transaction. If the problem persists, contact My Oracle Support.

BEA-110454
The administrative request to locally roll back the transaction {0} failed because the transaction is in an invalid state. {1}

Category:
JTA

Cause:
The administrative request is invalid.

Action:
Issue a forced commit operation instead to resolve the transaction.

BEA-110455
The administrative request to globally roll back the transaction {0} failed because the transaction is in an invalid state. {1}

Category:
JTA

Cause:
The administrative request is invalid.

Action:
Issue a forced commit operation instead to resolve the transaction.

BEA-110456
The administrative request to locally commit the transaction {0} failed because the transaction is in an invalid state. {1}

Category:
JTA

Cause:
The administrative request is invalid.

Action:
Issue a forced rollback operation instead to resolve the transaction.

BEA-110458
The administrative request to globally roll back the transaction {0} failed, because the coordinator {1} could not be contacted. {2}

Category:
JTA

Cause:
The coordinating server for the transaction is either not running or is unreachable.

Action:
Verify that the coordinating server is available and retry the operation. Alternatively, perform local operations to resolve the transaction.

BEA-110459
The administrative request to globally commit the transaction {0} failed, because the coordinator at {1} could not be contacted. {2}

Category:
JTA

Cause:
The coordinating server for the transaction is either not running or is unreachable.

Action:
Verify that the coordinating server is available and retry the operation. Alternatively, perform local operations to resolve the transaction.

BEA-110460
The administrative request to globally rollback the transaction {0} failed, because the coordinator does not support manual transaction resolution.

Category:
JTA

Cause:
The coordinating server is an older version of WebLogic Server that does not support manual transaction resolution.

Action:
Perform local commit operations on all participants that support manual transaction resolution.

BEA-110462
The administrative request to locally commit the transaction {0} failed, because the transaction has been marked for rollback.

Category:
JTA

Cause:
The transaction has been marked for rollback by an application component.

Action:
Attempt to resolve the transaction by using a forced rollback operation instead.

BEA-110464
The forced commit operation for transaction {0} on resource {1} was not performed, because the resource is busy.

Category:
JTA

Cause:
There may be a blocked resource operation for this transaction. The resource may be experiencing problems or it may be slow to respond.

Action:
Attempt to retry the commit operation. The associated resource changes for the transaction may need to be manually resolved using a resource-specific utility.

BEA-110465
The forced rollback operation for transaction {0} on resource {1} was not performed, because the resource is busy

Category:
JTA

Cause:
There may be a blocked resource operation for this transaction. The resource may be experiencing problems or it may be slow to respond.

Action:
Attempt to retry the commit operation. The associated resource changes for the transaction may need to be manually resolved using a resource-specific utility.

BEA-110466
The forced commit operation for transaction {0} on resource {1} was not performed because the resource has already been committed.

Category:
JTA

Cause:
The transaction may have completed before the administrative client invoked the commit operation.

Action:
No action is required. The transaction has been resolved.

BEA-110467
The forced rollback operation for transaction {0} on resource {1} was not performed because the resource has already been rolled back.

Category:
JTA

Cause:
The transaction may have completed before the administrative client invoked the rollback operation.

Action:
No action is required. The transaction has been resolved.

BEA-110468
The forced commit operation for transaction {0} on resource {1} encountered an error. {2}

Category:
JTA

Cause:
Refer to the resource exception in the error message and any appropriate resource-specific error logs.

Action:
Determine if administrative operations are required in the resource to resolve the transaction branch.

BEA-110469
The forced rollback operation for transaction {0} on resource {1} encountered an error. {2}

Category:
JTA

Cause:
Refer to the resource exception in the error message and any appropriate resource-specific error logs.

Action:
Determine if administrative operations are required in the resource to resolve the transaction branch.

BEA-110470
User [{0}] is not authorized to invoke a forced global rollback.

Category:
JTA

Cause:
The authenticated principal making the request does not have adequate privileges to perform a forced rollback operation on the transaction.

Action:
Authenticate using an identity with adequate privileges prior to invoking the operation.

BEA-110471
User [{0}] is not authorized to invoke a forced global commit.

Category:
JTA

Cause:
The authenticated principal making the request does not have adequate privileges to perform a forced commit operation on the transaction.

Action:
Authenticate using an identity with adequate privileges prior to invoking the operation.

BEA-110472
User [{0}] is not authorized to invoke a forced local rollback.

Category:
JTA

Cause:
The authenticated principal making the request does not have adequate privileges to perform a forced rollback operation on the transaction.

Action:
Authenticate using an identity with adequate privileges prior to invoking the operation.

BEA-110473
User [{0}] is not authorized to invoke a forced local commit.

Category:
JTA

Cause:
The authenticated principal making the request does not have adequate privileges to perform a forced commit operation on the transaction.

Action:
Authenticate using an identity with adequate privileges prior to invoking the operation.

BEA-110474
Unable to advertise non-XA resource {0}: {1}

Category:
JTA

Cause:
There may be a problem with the JNDI provider, or another object is already bound to this context.

Action:
Contact My Oracle Support.

BEA-110475
User [{0}] is not authorized to invoke commit on a non-XA resource transaction branch.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that client software is not directly invoking an internal WebLogic Server system object.

BEA-110476
The server has detected pending transactions during graceful shutdown. The server will wait for the pending transactions to complete before suspending the RMI service. A forced shutdown command can be issued to shut down the server immediately.

Category:
JTA

Cause:
The server has detected pending transactions during graceful shutdown.

Action:
No action is required. Use a forced shutdown command to ignore inflight work and shut down the server immediately.

BEA-110477
The unregisterResource operation for resource {0} timed out after {1} seconds.

Category:
JTA

Cause:
It was requested that the specified resource be unregistered from the transaction manager and transactions that refer to the resource still exist on the server.

Action:
Monitor inflight transactions to determine if there are still active transactions that depend on the unregistered resource. Options include using the Administration Console to manually resolve dependent transactions, or the resource may be redeployed for a sufficient period to allow the dependent transactions to complete.

BEA-110478
One-phase transaction [{1}] is in an unknown state for logging resource [{0}]. The transaction operations either all rolled back, or all committed, or are blocked. Transaction detail: [{2}]. Root cause: [{3}].

Category:
JTA

Cause:
If the logging last resource is a database, there are a number of possible root causes. Among them are: the database may have shut down or crashed during the call to local commit, the database connection may have failed, the database local transaction may have timed out, or the database may have detected a potential deadlock condition introduced by application operations within the local commit.

Action:
Examine the exception caused by the LLR resource to determine the root cause of the problem.

BEA-110479
Two-phase transaction [{1}], with logging resource [{0}], is an unknown state. The transaction manager will periodically retry determining the state of the transaction every [{3}] seconds. When the state is determined, the remaining resources in the transaction will be either rolled back or committed accordingly. Transaction detail: [{2}]. Root cause: [{4}].

Category:
JTA

Cause:
If the logging last resource is a database, there are a number of possible root causes. Among them are: the database may have shutdown or crashed during the call to local commit, the database connection may have failed, the database local transaction may have timed out, or the database may have detected a potention dead-lock condition introduced by application operations within the local commit.

Action:
Examine the exception caused by the LLR resource to determine the root cause of the problem. Note that no action may be required as the transaction manager will periodically retry the transaction until it can automatically rollback or commit accordingly.

BEA-110480
The transaction manager is completing logging resource [{0}] transaction [{1}]. The transaction, which was previously in an unknown state, is now resolved and in the [{2,choice,0#rollback|1#commit}] state.

Category:
JTA

Cause:
See previous log messages for the same transaction to determine the root cause.

Action:
See previous log messages for the same transaction to determine the root cause.

BEA-110482
A logging last resource (LLR) failed during initialization. The server cannot boot unless all configured LLRs initialize. Failing reason: {0}

Category:
JTA

Cause:
If the logging last resource is a JDBC LLR connection, there are a number of possible root causes. Among them are: the database may have shut down or crashed, the database connection may have failed during boot, or the database connection may have incorrect database permissions.

Action:
Examine the root exception thrown by the LLR to determine the root cause of the problem.

BEA-110483
The JTA health state has changed from {0} to {1}.

Category:
JTA

Cause:
An internal event has caused the JTA health state to transition to the normal state. Refer to previous health log entries for the conditions that have been corrected to trigger the state change.

Action:
No action is required.

BEA-110484
The JTA health state has changed from {0} to {1} with reason codes: {2}.

Category:
JTA

Cause:
Refer to the message body for information regarding the events that caused the health change.

Action:
Refer to the message body for the cause of the JTA state change and take the appropriate action to correct the exception condition.

BEA-110485
The JTA health state has changed from {0} to {1} with reason codes: {2}.

Category:
JTA

Cause:
Refer to the message body for information regarding the events that caused the health change.

Action:
Refer to the message body for the cause of the JTA state change and take the appropriate action to correct the exception condition.

BEA-110486
Transaction {0} cannot complete commit processing because resource [{1}] is unavailable. The transaction will be abandoned after {2} seconds unless all resources acknowledge the commit decision.

Category:
JTA

Cause:
The resource may have been undeployed or is unresponsive and declared unavailable.

Action:
Check for related server log messages that may provide additional details regarding the state of the resource. If the resource is undeployed, deploy the resource or the application module if the resource is application scoped. If a problem exists with the resource manager, correct the problem and redeploy the resource.

BEA-110487
Transaction {0} cannot complete rollback processing because the pending resource [{1}] is unavailable. The transaction will be abandoned after {2} seconds unless all resources acknowledge the rollback decision.

Category:
JTA

Cause:
The resource may have been undeployed or is unresponsive and declared unavailable.

Action:
Check for related server log messages that may provide additional detail regarding the state of the resource. If the resource is undeployed, deploy the resource or the application module if the resource is application scoped. If a problem exists with the resource manager, correct the problem and redeploy the resource.

BEA-110488
The LLR resource(s) {0} are not available and may contain transaction commit records required for recovery processing. Recovery of XA resources will not occur until these resources are deployed.

Category:
JTA

Cause:
Prior to server restart, one or more global transactions were processed that had a LLR participant and may not have completed before the server was restarted. This potentially left a commit record in a LLR resource and prepared resource transaction branches that are awaiting a commit or rollback decision from the coordinator.

Action:
Redeploy the specified LLR resources, wait for all in progress transactions to complete, and shut down the server gracefully.

BEA-110490
User [{0}] is not authorized to invoke Commit on a Coordinator.

Category:
JTA

Cause:
This might be a symptom of a potential security attack, or alternately, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-110491
User [{0}] is not authorized to invoke AckPrePrepare on a Coordinator.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-110492
User [{0}] is not authorized to invoke CheckStatus on a Coordinator.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-110493
User [{0}] is not authorized to invoke AckCommit on a Coordinator.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-110494
User [{0}] is not authorized to invoke NakCommit on a Coordinator.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-110495
User [{0}] is not authorized to invoke AckRollback on a Coordinator.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-110496
User [{0}] is not authorized to invoke NakRollback on a Coordinator.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-110500
User [{0}] is not authorized to invoke GetSubCoordinatorInfo on a SubCoordinator.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-110501
User [{0}] is not authorized to invoke GetProperties on a SubCoordinator.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-110502
User [{0}] is not authorized to invoke Recover on a SubCoordinator.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-110503
The migrator (the Administration Server for manual JTA migration policy or the Singleton Master for automatic JTA migration policy) is not available. Will skip JTA TRS failback because isStrictOwnershipCheck is [false]. This may lead to potencial TLOG corruption if the TRS of {0} has been migrated to a backup server and the backup server is accessing the TLOG of {0}. More safety can be achieved by setting isStrictOwnershipCheck to [true].

Category:
JTA

Cause:
The Administration Server or Singleton Master is not running or cannot be reached.

Action:
Start Administration Server or Singleton Master before starting any Managed Server in the cluster.

BEA-110504
There was an error advertising TransactionSynchronizationRegistry object: {0}.

Category:
JTA

Cause:
There may be a problem with the JNDI provider or another object is already bound to this context.

Action:
Contact My Oracle Support.

BEA-110505
An attempt was made to set an invalid TRANSACTION_COMPLETION_TIMEOUT_SECONDS_PROPERTY_KEY for transaction property: keys must be number and values must be between -1 and max value of integer.

Category:
JTA

Cause:
See the message detail.

Action:
Change the application to assign the proper TRANSACTION_COMPLETION_TIMEOUT_SECONDS_PROPERTY_KEY property value.

BEA-111001
The Transaction Manager is being started in standalone mode and will not be able to participate in distributed transactions.

Category:
JTA

Cause:
There are no suitable RMI or JNDI providers configured.

Action:
Configure the appropriate RMI and JNDI context providers.

BEA-111002
The Transaction Manager is being started in distributed mode.

Category:
JTA

Cause:
The Transaction Manager is in distributed mode and can participate in distributed transactions.

Action:
No action is required.

BEA-111003
An error occurred while creating the transaction log persistent store: {1}.

Category:
JTA

Cause:
Refer to the associated exception for the cause.

Action:
No action is required.

BEA-111004
Transaction could not set CoordinatorURL to use AdminChannel downgrading {0}.

Category:
JTA

Cause:
An error occurred while trying to set CoordinatorURL to use AdminChannel.

Action:
Check for other log messages that give more information about the failure.

BEA-111005
An in-progress XA operation for transaction {0} on resource {1} could not complete within {2} seconds, or was interrupted. Allowing subsequent calls to proceed.

Category:
JTA

Cause:
The call to the resource manager may have been affected by a server or network problem and could have been interrupted.

Action:
Verify that the resource manager is functioning properly and is accessible.

BEA-111006
Transaction could not set CoordinatorURL to use SSL URL downgrading {0}

Category:
JTA

Cause:
An error occurred while trying to set CoordinatorURL to use the SSL port.

Action:
Check for other log messages that give more information about the failure.

BEA-111007
The commit operation for one-phase transaction {0} on resource {1} encountered an error. {2}

Category:
JTA

Cause:
Refer to the resource exception in the error message and any appropriate resource-specific error logs.

Action:
Determine if administrative operations are required in the resource to resolve the transaction branch.

BEA-111008
Transaction Log failed during initialization. The server cannot boot unless Transaction Log initialize. Failing reason: {0}

Category:
JTA

Cause:
The transaction log may contain transaction records for committed two-phase transactions that have not completed committing all resources involved in the transaction..

Action:
Check for other log messages that give more information about the failure.

BEA-111009
activateDeployments failed during initialization. Failing reason: {0}

Category:
JTA

Cause:
During WLS start up, an exception was caught at activateDeployemts.

Action:
Check for other log messages that give more information about the failure.

BEA-111010
SetPrimaryStore failed. Failing reason: {0}

Category:
JTA

Cause:
An exception was caught at setPrimaryStore.

Action:
Check for other log messages that give more information about the failure.

BEA-111011
A Transaction Log PrimaryStore failed during initialization. The server cannot boot unless configured Transaction Log Primary Store initialize. Failing reason: {0}

Category:
JTA

Cause:
The Transaction Log Primary Store may contain transaction records for committed two-phase transactions that have not completed committing all resources involved in the transaction.

Action:
Examine the root exception thrown by the Transaction Log Primary Store to determine the root cause of the problem.

BEA-111012
SetPrimaryStore close failed when retry. Failing reason: {0}

Category:
JTA

Cause:
An exception was caught at close store in retrying setPrimaryStore .

Action:
Check for other log messages that give more information about the failure.

BEA-111013
Recover JDBCStore init store exception: {0}

Category:
JTA

Cause:
An exception occurred when init store.

Action:
Check for other log messages that give more information about the failure.

BEA-111014
There is a naming conflict for resource = [{0}]. This resource is being registered by this server and has already been registered in: [{1}].

Category:
JTA

Cause:
This resource is trying to be registered as a NonXAResource but was already registered as an XAResource.

Action:
Correct the configuration either by making the resource name unique or by making the resource consistently either an XAResource or a NonXAResource.

BEA-111015
The commit operation for transaction {0} timed out after {1} seconds.

Category:
JTA

Cause:
The application may take longer than the time that is specified in timeout-seconds in the JTA parameter before issuing the commit.

Action:
Increase the transaction timeout-seconds in the JTA parameter or tuning application.

BEA-111016
Recovery is not possible as determiner resource can not be obtained {0}.

Category:
JTA

Cause:
Determiner resource may have been removed or is otherwise unobtainable.

Action:
Insure determiner resource can be obtained and has not been removed.

BEA-111017
Encountered an exception while attempting to acquire a transaction manager for transactional annotation interceptors {0}.

Category:
JTA

Cause:
Examine the root exception to determine the cause of the problem.

Action:
Take appropriate action based on the cause.

BEA-111018
No ComponentInvocation is present for @Transactional annotation processing. The restriction on use of UserTransaction will not be enforced.

Category:
JTA

Cause:
No ComponentInvocation is present for @Transactional annotation processing.

Action:
No action is required.

BEA-111019
The server has detected pending transactions after graceful shutdown in ClientInitiatexTxShutdownService.stop. Continue to work.

Category:
JTA

Cause:
The server has detected pending transactions after graceful shutdown in ClientInitiatexTxShutdownService.stop. Continue to work.

Action:
No action is required. Use a forced shutdown command to ignore inflight work and shut down the server immediately.

BEA-111020
An issue occurred during cross-site recovery processing: {0}.

Category:
JTA

Cause:
A lease store connection or other failures has occurred.

Action:
Refer to logs for information on the cause of failure.

BEA-111021
The JTA Security Interoperability Mode value "compatibility" is deprecated. Use "default" or "performance" instead.

Category:
JTA

Cause:
The domain JTA configuration specifies a value of "compatibility" for Security Interoperability Mode.

Action:
Modify the domain JTA configuration to specify a value of "default" or "performance" for Security Interoperability Mode.

BEA-114089
User [{0}] is not authorized to invoke ackPrepare on a Coordinator.

Category:
JTA

Cause:
This might be a symptom of a potential security attack or, alternatively, a problem with the "system" security identity of the server.

Action:
Verify that the client software is not directly invoking an internal WebLogic Server system object.

BEA-119000
One-phase transaction [{1}] for logging last resource [{0}] is in an unknown state.

Category:
JTAExceptions

Cause:
If the LLR is a database, there are a number of possible root causes. Among them are: the database may have shut down or crashed during the call to local commit, the database connection may have failed, the database local transaction may have timed out, or the database may have detected a potential deadlock condition introduced by application operations within the local commit.

Action:
Examine the root exception generated by the LLR to determine the root cause of the problem.

BEA-119001
Two-phase transaction [{1}] for logging last resource [{0}] is in an unknown state.

Category:
JTAExceptions

Cause:
If the LLR is a database, there are a number of possible root causes. Among them are: the database may have shut down or crashed during the call to local commit, the database connection may have failed, the database local transaction may have timed out, or the database may have detected a potential deadlock condition introduced by application operations within the local commit.

Action:
Examine the root exception generated by the LLR resource to determine the root cause of the problem.

BEA-119002
A LLR failed during initialization. The server cannot boot unless all configured LLRs initialize. Failing reason: {0}

Category:
JTAExceptions

Cause:
If the LLR is a JDBC LLR connection, there are a number of possible root causes. Among them are: the database may have shut down or crashed, the database connection may have failed during boot, or the database connection may have incorrect database permissions.

Action:
Examine the root exception generated by the LLR resource to determine the root cause of the problem.

BEA-119003
LLR [{0}] failed during initialization, as one of its records is corrupted. Failure reason: {1}

Category:
JTAExceptions

Cause:
The cause is unknown, but could be possible disk corruption.

Action:
Examine the root exception generated by the LLR to determine the root cause of the problem. Possible solutions are: restore LLR resource tables from backup, delete the failing LLR table (which risks producing heuristic hazards), or contact My Oracle Support.

BEA-119004
The user-preferred server of JTAMigratableTargetMBean [{0}] cannot be set to [{1}].

Category:
JTAExceptions

Cause:
The value of the user-preferred server is invalid. It must be [{0}].

Action:
Change the value of the user-preferred server of JTAMigratableTargetMBean [{0}] from [{1}] to [{0}].

BEA-119005
JTA subsystem failed. A forced shutdown of the server was done because the server is in automatic JTA migration mode.

Category:
JTAExceptions

Cause:
The JTA subsystem failed.

Action:
JTA Transaction Recovery Service will be automatically migrated to back up the server.

BEA-119006
A Transaction Log Primary Store failed during initialization. The server cannot boot unless the configured Transaction Log Primary Store initialize. Failing reason: {0}

Category:
JTAExceptions

Cause:
See the message detail.

Action:
Examine the root exception generated by the Transaction Log Primary Store to determine the root cause of the problem.

BEA-130000
Insertion of {0} into XML entity cache rejected. Entity size, {1}, exceeded cache size, {2}.

Category:
XML

Cause:
The cache may be too small or a specific item might be very large. The worst case is that this indicates a denial of service attack.

Action:
No action is required. However, performance will be best if items are cached.

BEA-130001
Entity cache appears to be broken. This impacts the performance of XML parsing.

Category:
XML

Cause:
Unknown

Action:
No action is required. However, performance will increase if items are cached. Also the cache provides a backup in the case of a network failure. While the cache is not operating, this backup is not in effect.

BEA-130002
The entity that was just put in the cache cannot be retrieved: "{0}". Timeout may be too short.

Category:
XML

Cause:
Usually this indicates that the entity timeout was set to a very small value. Otherwise, there is some unknown problem with the cache module itself.

Action:
No action is required, but XML parse performance will be impacted. Also, there is no cached copy to act as a backup in the event of a network failure.

BEA-130003
Could not instantiate the specified factory class. {0}.

Category:
XML

Cause:
The class name of the factory was not correct or it was not in the CLASSPATH.

Action:
Check the CLASSPATH or verify the Administration Console entry or MBean value.

BEA-130006
XML cache warning for registry {0}: entry rejection due to entry being larger than the cache memory size. entry: {1} Entry memory size: {2}

Category:
XML

Cause:
The entry is larger than the cache.

Action:
No action is required unless the item should be cached next time. If so, increase the cache memory size.

BEA-130007
XML cache event: memory purge of {0} entries of combined size {1}. Current memory usage is {2} bytes.

Category:
XML

Cause:
This is an information message.

Action:
No action is required.

BEA-130008
XML cache event: disk purge of {0} entries of combined size {1}. Current disk usage is {2} bytes.

Category:
XML

Cause:
This is an information message.

Action:
No action is required.

BEA-130009
XML cache warning for registry {0}: entry persist attempt rejected due to entry being larger than the cache disk size. Status changed to transient. entry: {1} entry disk size: {2}

Category:
XML

Cause:
The size of the entry on the disk exceeds the allocated disk space.

Action:
No action is required. If the entry should be persisted next time, increase the disk size of the cache.

BEA-130010
XML cache event for registry {0}: entry added. entry: {1}, entry memory size: {2}, storage type: {3}, current memory usage (bytes): {4}

Category:
XML

Cause:
This is an information message.

Action:
No action is required.

BEA-130011
XML cache event for registry {0}: entry deleted. entry: {1}, entry memory size: {2}, entry disk size: {3}, current memory usage (bytes): {4}, current disk usage (bytes): {5}

Category:
XML

Cause:
This is an information message.

Action:
No action is required.

BEA-130012
XML cache event for registry {0}: entry persisted. entry: {1}, entry disk size: {2}, current disk usage (bytes): {3}

Category:
XML

Cause:
This is an information message.

Action:
No action is required.

BEA-130013
XML cache event for registry {0}: entry loaded. entry: {1}, entry memory size: {2}, current memory usage (bytes): {3}

Category:
XML

Cause:
This is an information message.

Action:
No action is required.

BEA-130014
XML cache event: statistics checkpointed.

Category:
XML

Cause:
This is an information message.

Action:
No action is required.

BEA-130015
XML cache event: cache created. current memory usage (bytes): {0}, current disk usage (bytes): {1}

Category:
XML

Cause:
This is an information message.

Action:
No action is required.

BEA-130016
XML cache event: cache loaded. Current memory usage (bytes): {0}, current disk usage (bytes): {1}

Category:
XML

Cause:
This is an information message.

Action:
No action is required.

BEA-130017
XML cache event: cache closed. current disk usage (bytes): {0}

Category:
XML

Cause:
This is an information message.

Action:
No action is required.

BEA-130018
XML cache error: cache file {0} is corrupted. Creating new cache from scratch.

Category:
XML

Cause:
The cache file was corrupted. This normally does not occur.

Action:
The server should be restarted. If a backup of the cache files exists, restore the cache files, and then restart the server.

BEA-130019
XML cache error for registry {0}: entry file {1} is corrupted. Removing from cache. entry: {2}

Category:
XML

Cause:
The cache file was corrupted. This normally does not occur.

Action:
The server should be restarted. The entry will be re-cached on the next access of the server.

BEA-130020
XML cache error: statistics file {0} is corrupted, reinitializing. Previous statistics are lost.

Category:
XML

Cause:
The cache file was corrupted. This normally does not occur.

Action:
The server should be restarted.

BEA-130021
XML cache error for registry {0}: entry file {1} cannot be written. Status changed to transient. entry: {2}

Category:
XML

Cause:
This is often a file protection issue.

Action:
Determine why the file cannot be saved and make the appropriate adjustments.

BEA-130022
XML cache error: cache file {0} cannot be written.

Category:
XML

Cause:
This is often a file protection issue.

Action:
Determine why the file cannot be saved and make the appropriate adjustments.

BEA-130023
XML cache error: statistics file {0} cannot be written. There are no futher cache statistics for this session.

Category:
XML

Cause:
This is often a file protection issue.

Action:
Determine why the file cannot be saved and make the appropriate adjustments.

BEA-130024
XML cache error for registry {0}: out of memory loading entry. Entry removed from cache. entry: {1}, file: {2}

Category:
XML

Cause:
The entry might be unusually large or perhaps the JVM heap size is too small.

Action:
Check the size of the rejected entry. If entries of that size need to be handled, increase the heap size.

BEA-130025
XML cache error: out of memory loading cache. Cache not opened. file: {0}

Category:
XML

Cause:
The cache file is not large, so memory usage is almost full.

Action:
Increase the JVM heap size.

BEA-130026
XML cache error: out of memory loading statistics. File: {0}

Category:
XML

Cause:
The cache file is not large, so memory usage is almost full.

Action:
Increase the JVM heap size.

BEA-130027
XML cache warning: the requested memory size of the XML cache, {0}, exceeds the available memory, {1}.

Category:
XML

Cause:
Either the provided parameters are not in sync with the usage, or a lot of the available memory is being used.

Action:
Reduce the cache size or increase the JVM heap size. If there should be more available memory, determine what is using all of the available memory.

BEA-130028
XML cache warning: the requested memory size of the XML cache, {0}, is a large percentage of the available memory, {1}.

Category:
XML

Cause:
Either the provided parameters are not in sync with the usage, or something is using a lot of the available memory.

Action:
Reduce the cache size or increase the JVM heap size. If there should be more available memory, determine what is using all of the available memory.

BEA-130029
XML cache error: an unexpected error occurred in the XML cache. {0}

Category:
XML

Cause:
The cause is unknown.

Action:
Refer to the associated text at the end of the message and contact My Oracle Support for help resolving the error.

BEA-130030
XML cache error for registry {0}: the file, {1}, representing entry {2} cannot be read.

Category:
XML

Cause:
The file is read-protected.

Action:
Check the access rights of the file and make the appropriate changes.

BEA-130031
XML cache error: the cache file, {0}, cannot be read.

Category:
XML

Cause:
The file is read-protected.

Action:
Check the access rights of the file and make the appropriate changes.

BEA-130032
XML cache error: statistics file {0} cannot be read.

Category:
XML

Cause:
The file is read-protected.

Action:
Check the access rights of the file and make the appropriate changes.

BEA-130033
Parser or DocumentBuilder cannot be created to satisfy the configuration requested. {0}

Category:
XML

Cause:
The configuration was invalid.

Action:
Verify that the factory that creates the parser and the properties or features set on this parser are configured properly.

BEA-130034
Failed to parse the given XML document. {0}

Category:
XML

Cause:
An error occurred in the structure of the XML document.

Action:
Verify the XML syntax of the document.

BEA-130035
Failed to open XML document. {0}

Category:
XML

Cause:
The file does not exist.

Action:
Check the file name, the file location and its associated permissions.

BEA-130036
Initializing XMLRegistry

Category:
XML

Cause:
This is an information message.

Action:
No action is required.

BEA-130037
The stack trace associated with message {0} follows:

Category:
XML

Cause:
An error condition was reported.

Action:
No action is required.

BEA-130039
The warning message:

Category:
XML

Cause:
An warning condition was reported.

Action:
No action is required.

BEA-140008
Internal error. Failed to save configuration changes to the configuration repository - {0}.

Category:
Management

Cause:
The config.xml file is either write-protected, or the user that started the server is not authorized to write to this file or directory.

Action:
Ensure that the operating system user who starts the server has authorization to write to the config.xml file and that the config.xml file is not write-protected.

BEA-140013
{0}

Category:
Management

Cause:
This is an informational message.

Action:
No action is required.

BEA-141009
Error occurred in the file distribution servlet while processing the request type "{0}", {1}.

Category:
Management

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Take action based upon the provided exception details.

BEA-141010
Error occurred in the file distribution servlet and received an unacceptable request of type "{0}".

Category:
Management

Cause:
An invalid request was made to the file distribution servlet.

Action:
This is an internal WebLogic Server error. No action is required.

BEA-141011
The file distribution servlet failed to distribute the security properties file, because the file was not found at the configured location: {0}.

Category:
Management

Cause:
The identified file was not available to the Administration Server.

Action:
Verify the configuration of this file.

BEA-141021
The cluster property {0} was ignored because the server is not part of a cluster.

Category:
Management

Cause:
A non-applicable cluster property was specified at server startup.

Action:
Modify the configuration to identify that this Managed Server is, in fact, a member of a cluster, or eliminate the specification of the cluster property from the start command.

BEA-141023
An error occurred while setting the attribute value in the MBean proxy {0}, method {1} with value {2} ({3}).

Category:
Management

Cause:
An invalid attribute value was specified.

Action:
Verify that the provided attribute value (specified either in the configuration or through a dynamic setting) is correct.

BEA-141051
The operation failed with message: {0}.

Category:
Management

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Take action based upon the details of the provided error message.

BEA-141052
The auto deployment poller has started.

Category:
Management

Cause:
This is an informational message.

Action:
No action is required.

BEA-141053
The auto deployment poller has not started for the production server.

Category:
Management

Cause:
This is an informational message.

Action:
No action is required.

BEA-141062
The user does not have permission to perform {1} operation on MBean {0}. Method = {3}, attribute = {2}

Category:
Management

Cause:
No access control list (ACL) permissions are defined for the user to complete this operation.

Action:
The system administrator must add ACL permissions in order for the user to perform this operation.

BEA-141063
The user does not have permission to perform {1} operation on MBean {0}. Method: {2}.

Category:
Management

Cause:
The user has no defined access control list (ACL) to perform this MBean operation.

Action:
The system administrator must define permissions in order for the user to perform this MBean operation.

BEA-141071
The file distribution servlet failed to distribute the embedded LDAP initial replica data file because the file was not found at the configured location: {0}.

Category:
Management

Cause:
This is an internal WebLogic Server error that should not occur during normal operation.

Action:
Contact My Oracle Support.

BEA-141073
Migration task ({0}) - {1}

Category:
Management

Cause:
This is an informational message.

Action:
No action is required.

BEA-141076
No module with URI ({1}) was found in ({0}).

Category:
Management

Cause:
The application is potentially misconfigured relative to this module.

Action:
Verify that the application archive and its descriptors are correctly configured.

BEA-141077
An error occurred during the parsing of descriptors for {0}. Exception {1} occurred.

Category:
Management

Cause:
Refer to the exception details for the exact cause of this parsing error.

Action:
Take action based upon provided exception details to either correct the identified component or its descriptors.

BEA-141078
A descriptor initialization error occurred for module {0} in EAR file {1}. Creation of the temporary file {2} failed.

Category:
Management

Cause:
The extraction of the EAR file failed due to an I/O error. See the logged for details.

Action:
Ensure that the file referred to in the exception can be created, and there is no directory by the same name.

BEA-141081
The file distribution servlet failed to distribute the embedded LDAP initial replica data file due to the following error: {0}.

Category:
Management

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Take action based upon the provided exception details.

BEA-141086
An error occurred while setting a value for {0}.

Category:
Management

Cause:
The specified command line property provided an invalid value for attribute {0}.

Action:
Verify that the specified command line property provides a valid attribute value.

BEA-141087
Property: {0} is not a recognized MBean attribute or special property used for management. It is most likely being used by subsystems and will continue to work as expected if it is a supported option.

Category:
Management

Cause:
An unrecognized property has been specified on the start command.

Action:
Eliminate the invalid properties from the start command.

BEA-141089
Starting the server based on the WebLogic Server 6.x configuration directory structure.

Category:
Management

Cause:
The startup directory does not contain the config.xml configuration file. The file was located in the config/domain directory.

Action:
Start the server from the directory that contains the domain configuration file.

BEA-141102
Subject: {0} does not have access to perform {1} actions.

Category:
Management

Cause:
Either the named subject is not allowed to perform this action and is appropriately being denied this access, or the named subject should be allowed to perform this action and the role membership of the subject is not properly configured.

Action:
Contact the system administrator to modify role definitions.

BEA-141107
Version: {0}

Category:
Management

Cause:
This is normal system initialization processing.

Action:
No action is required.

BEA-141124
An invalid system property was specified while booting the server {0}.

Category:
Management

Cause:
The server might have been started using an invalid system property. For example, starting the server using java -D weblogic.Server will generate this exception.

Action:
Correct the invalid system property.

BEA-141126
The configuration file {0} is read-only.

Category:
Management

Cause:
This occurs when the write permissions on the file are not set to allow the user that booted the server to write to the config.xml file. Write access is often intentionally denied in production environments.

Action:
In many cases, write access is intentionally denied. In such cases, this is just an informational message. If the file needs to be writable, change the permissions on the file or ask the system administrator to do so.

BEA-141133
The Name attribute cannot be modified after the MBean {0} has been created.

Category:
Management

Cause:
The Name attribute is being modified by a setName operation.

Action:
Specify the name of the MBean during creation.

BEA-141145
An attempt was made to connect to the Administration Server without credentials.

Category:
Management

Cause:
The requirement to supply credentials on all requests was added in version 8.1 of the product. It is most likely that an old version of a utility is being used that is not properly supplying these credentials. It is also possible that this represents an attempt to compromise the server.

Action:
Determine the source of the request. If it is a legitimate request, ensure that updated software is being used which properly supplies the credentials. It is also important to restrict access to the Administration Server. Refer to the WebLogic Server documentation to ensure that all of the proper security precautions have been taken.

BEA-141146
An attempt was made to connect to the Administration Server by the user {0} and a password which does not match.

Category:
Management

Cause:
The requirement to supply credentials on all requests was added in version 8.1 of the product. In this case, the password is not valid for the specified user. This may be the result of supplying an improper user name and password when using the deployment utilities.

Action:
Determine the source of the request. If it is a legitimate request, ensure that updated software which properly supplies the credentials is in use. It is also important to restrict access to the Administration Server. Refer to the WebLogic Server documentation to ensure that all of the proper security precautions have been taken.

BEA-141147
An attempt was made to upload a file to the Administration Server by the unauthorized user {0}.

Category:
Management

Cause:
The requirement to supply credentials on all requests was added in version 8.1 of the product. In this case, the user specified is not configured with the authorization to upload files.

Action:
To enable the user to upload files to the Administration Server, it is necessary that the user be added to the administrator or deployer role. Alternatively, it is possible to authorize a user specifically for "FileUpload". Consult the WebLogic Server documentation for instructions on how to do this.

BEA-141148
An invalid attempt was made to download a {1} resource from the Administration Server by the unauthorized user {0}.

Category:
Management

Cause:
The requirement to supply credentials on all requests was added in version 8.1 of the product. In this case, the credentials of the user that is being used to boot the Managed Server are used to authorize the request. That user is not authorized to access files of the type {1}.

Action:
Ensure that the proper credentials are being used to initiate the connection. In most cases, this involves ensuring that the credentials being used to boot the Managed Server are properly authorized on the Administration Server.

BEA-141149
An invalid attempt was made to connect to the Administration Server with a salt of {0} and a signature of {1}, likely due to private key mismatch or clock skew between servers.

Category:
Management

Cause:
The requirement to supply credentials on all requests was added in version 8.1 of the product. In this case, the password is not valid for the specified user or the nonce has expired. This may be the result of supplying an improper user name and password when using the deployment utilities.

Action:
Determine the source of the request and ensure that the Managed Server and the Administration Server share the same security credential. That credential is stored in the domain configuration and distributed at server startup. In this case, where the Managed Server is booted using a configuration that is different from that of the Administration Server, perhaps in Managed Server independence mode. Refer to the WebLogic Server documentation to ensure that all of the proper security precautions have been taken. Verify that clock skew has not occurred between the servers in the domain.

BEA-141151
The Administration Server could not be reached at {0}.

Category:
Management

Cause:
The Administration Server is not available at the specified URL or the URL is not specified in the correct format, such as http://myhost:7001.

Action:
Ensure that the Administration Server is running at the specified host and port. Check that the URL is specified in the correct format. The URL is specified by the protocol://host:port, for example http://myhost:7001.

BEA-141187
Java system properties are defined as follows: {0}.

Category:
Management

Cause:
This is an informational message.

Action:
No action is required.

BEA-141190
The commit phase of the configuration update failed with an exception.

Category:
Management

Cause:
An exception occurred during the commit of the update.

Action:
Retry the activate. Take action based upon the provided exception details.

BEA-141191
The prepare phase of the configuration update failed with an exception.

Category:
Management

Cause:
An exception occurred during the prepare of the update.

Action:
Ensure that the update is valid. Take action based upon the provided exception details, make any required changes, change the changes, and retry the activate.

BEA-141192
The read of the edit lock file failed with an exception.

Category:
Management

Cause:
An exception occurred during the read of the edit lock file.

Action:
Take action based upon the provided exception details. Try to get the edit lock again.

BEA-141193
The write of the edit lock file failed with an exception.

Category:
Management

Cause:
An exception occurred during the write of the edit lock file.

Action:
Take action based upon the provided exception details. Try to get the edit lock again.

BEA-141194
The registration of the configuration subsystem with the deployment subsystem failed with an exception.

Category:
Management

Cause:
An exception occurred during the registration of the configuration subsystem.

Action:
Take action based upon the provided exception details. Restart the server.

BEA-141196
The Managed Server could not update the configuration files during the registration with the deployment service. The update failed due to an exception.

Category:
Management

Cause:
An exception occurred during the update of configuration files.

Action:
Take action based upon the provided exception details, make any required changes, and try to restart the Managed Server.

BEA-141197
The deployment of {0} failed.

Category:
Management

Cause:
An exception occurred during a resource deployment.

Action:
Take action based upon the provided exception details, make any required changes, and try to restart the Managed Server.

BEA-141198
The undeployment of {0} failed.

Category:
Management

Cause:
An exception occurred during a resource undeployment.

Action:
Take action based upon the provided exception details, make any required changes, and try to restart the Managed Server.

BEA-141199
In the compatibility MBean server, the operation {1} on the MBean {0} modified the configuration without starting an edit session and activating the changes.

Category:
Management

Cause:
The impact information was incorrect for the MBean operation.

Action:
Contact My Oracle Support as this is an internal coding error that should not occur.

BEA-141200
Detected a domain that was created from an earlier release of WebLogic Server. The domain will be upgraded to the current {0} release.

Category:
Management

Cause:
This is an informational message.

Action:
No action is required.

BEA-141201
Unable to modify the configuration using the compatibility MBean server, as other changes are pending. Activate the pending changes before modifying the configuration with the compatibility MBean server.

Category:
Management

Cause:
The configuration was not modified because pending changes were present.

Action:
Activate the changes before using the compatibility server.

BEA-141202
The addition of the bean {0} failed during the activate phase because of {1}

Category:
Management

Cause:
See the exception message for more information.

Action:
Check the exception message for more detail.

BEA-141203
The addition of the bean {0} failed during the activate phase because of {1}

Category:
Management

Cause:
See the exception message for more information.

Action:
Check the exception message for more detail.

BEA-141204
The addition of the bean {0} failed during the activate phase because of {1}

Category:
Management

Cause:
See the exception message for more information.

Action:
Check the exception message for more detail.

BEA-141205
The removal of the bean {0} failed during the activate phase because of {1}

Category:
Management

Cause:
See the exception message for more information.

Action:
Check the exception message for more detail.

BEA-141206
The removal of the bean {0} failed during the activate phase because of {1}

Category:
Management

Cause:
See the exception message for more information.

Action:
Check the exception message for more detail.

BEA-141207
The removal of the bean {0} failed during the activate phase because of {1}

Category:
Management

Cause:
See the exception message for more information.

Action:
Check the exception message for more detail.

BEA-141208
The modification of the property {0} failed during the activate phase because of {1}

Category:
Management

Cause:
See the exception message for more information.

Action:
Check the exception message for more detail.

BEA-141209
The modification of the property {0} failed during the activate phase because of {1}

Category:
Management

Cause:
See the exception message for more information.

Action:
Check the exception message for more detail.

BEA-141210
The modification of the property {0} failed during the activate phase because of {1}

Category:
Management

Cause:
See the exception message for more information.

Action:
Check the exception message for more detail.

BEA-141211
An attempt to initialize the property {0} failed because of {1}

Category:
Management

Cause:
See the exception message for more information on the cause of this error.

Action:
The exception message may have more information about the action to take.

BEA-141212
An attempt to initialize the property {0} failed because of {1}

Category:
Management

Cause:
See the exception message for more information on the cause of this error.

Action:
The exception message may have more information about the action to take.

BEA-141213
An attempt to initialize the property {0} failed because of {1}

Category:
Management

Cause:
See the exception message for more information on the cause of this error.

Action:
The exception message may have more information about the action to take.

BEA-141214
The add of the bean {0} failed. The encountered exception was {1}

Category:
Management

Cause:
See the exception message for more information on the cause of this error.

Action:
The exception message may have more information about the action to take.

BEA-141215
The add of the bean {0} failed. The encountered exception was {1}

Category:
Management

Cause:
See the exception message for more information on the cause of this error.

Action:
The exception message may have more information about the action to take.

BEA-141216
The add of the bean {0} failed. The encountered exception was {1}

Category:
Management

Cause:
See the exception message for more information on the cause of this error.

Action:
The exception message may have more information about the action to take.

BEA-141217
The removal of the bean {0} failed. The encountered exception was {1}

Category:
Management

Cause:
See the exception message for more information on the cause of this error.

Action:
The exception message may have more information about the action to take.

BEA-141218
The removal of the bean {0} failed. The encountered exception was {1}

Category:
Management

Cause:
See the exception message for more information on the cause of this error.

Action:
The exception message may have more information about the action to take.

BEA-141219
The removal of the bean {0} failed. The encountered exception was {1}

Category:
Management

Cause:
See the exception message for more information on the cause of this error.

Action:
The exception message may have more information about the action to take.

BEA-141220
A required class was not found while upgrading the domain. This could be possible if the security provider JAR files were not upgraded to conform with WebLogic Server version 9.0. Upgrade these providers using java weblogic.Upgrade -type securityproviders.

Category:
Management

Cause:
The security provider JAR files were not upgraded to conform with new WebLogic Server 9.0 classes.

Action:
Run the upgrade tool to upgrade the provider.

BEA-141221
An error occurred while performing an undo of unactivated changes in the compatibility MBean server: {0}.

Category:
Management

Cause:
See the exception message for more information.

Action:
Check the exception message for more detail.

BEA-141223
The server name {0} specified with -Dweblogic.Name does not exist. The configuration includes the following servers {1}.

Category:
Management

Cause:
The -Dweblogic.Name command line property specifies a server that does not exist in the configuration.

Action:
Check the configuration for the list of configured servers.

BEA-141224
The Administration Server is not reachable.

Category:
Management

Cause:
This could be a network issue.

Action:
Check the status of the Administration Server.

BEA-141225
The delete of pending directory file {0} failed.

Category:
Management

Cause:
An error occurred while deleting the file.

Action:
Ensure that no processes have the file open for write.

BEA-141226
An invalid deployment service prepare callback with ID {0} was received.

Category:
Management

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-141227
Making a backup copy of the configuration at {0}.

Category:
Management

Cause:
This happens during certain server lifecycle transitions and during configuration changes.

Action:
No action is required.

BEA-141228
An attempt to back up the configuration to {0} failed with {1}.

Category:
Management

Cause:
See the message text for the exception message.

Action:
Check the exception information included in the message text.

BEA-141229
The upgrade process has been canceled by the user. The server process will not be started.

Category:
Management

Cause:
The server startup cannot proceed without upgrading the domain.

Action:
Upgrade the domain, and then start the server.

BEA-141230
Could not locate the descriptor file for System Resource: {0}.

Category:
Management

Cause:
The descriptor file could not be located in the specified path.

Action:
Ensure that the descriptor file is in the appropriate location.

BEA-141231
Could not register the JSR object: {0}.

Category:
Management

Cause:
There are many possible causes for this warning.

Action:
Look at the stack trace and take appropriate action.

BEA-141232
Could not decrypt the {1} attribute value of {2} from the file {0}. The edit session has been canceled. The decryption failed with the exception {3}.

Category:
Management

Cause:
An invalid encrypted value was found in the edit lock file.

Action:
Start a new edit session.

BEA-141233
Could not decrypt the edit lock file {0}. The edit session has been canceled. The decryption failed with the exception {1}.

Category:
Management

Cause:
An exception occurred when decrypting the edit lock file.

Action:
Start a new edit session.

BEA-141234
A rollback of a dynamic change failed. The message for the failure is "{0}". The cause of the exception is "{1}".

Category:
Management

Cause:
See the message body for the cause.

Action:
Look at the possible causes of this error. The cause may give some indication of the possible actions to take.

BEA-141237
Extraneous text found in the config.xml file: {0}.

Category:
Management

Cause:
This is generally caused by mistakes in hand-edited config.xml files. The config.xml file is a valid XML document, however, the extraneous text is not related to any MBean attributes.

Action:
Review the config.xml file for mistakes, such as extra delimeters near the text listed in the error message.

BEA-141238
A non-dynamic change has been made which affects the server {0}. This server must be rebooted in order to consume this change.

Category:
Management

Cause:
This happens when one or more of the changes made to the configuration affect non-dynamic settings. When this occurs, the affected Managed Servers are determined, and those servers are not updated when the change is activated. In order to consume the change, these servers must be rebooted.

Action:
Reboot the named server.

BEA-141239
The non-dynamic attribute {1} on {0} has been changed. This may require redeploying or rebooting configured entities.

Category:
Management

Cause:
This happens when one or more of the changes made to the configuration affect non-dynamic settings.

Action:
The required action, if any, will be indicated in a later log message.

BEA-141240
Found a version {0} config.cml file, but expected a version 9 or higher config.xml file. This could happen if an attempt to boot was made from the config directory rather than the domain root.

Category:
Management

Cause:
This could happen if an attempt was made to boot from the config directory rather than the domain root. Otherwise, the configuration could be corrupted.

Action:
Ensure that the config.xml file is not corrupted and that the boot is attempted from the domain root.

BEA-141241
Found a version {0} config.xml file, but expected a pre-version 9 config.xml file. This could happen if an attempt was made to boot from the config directory rather than the domain root.

Category:
Management

Cause:
This could happen if a 9.x config.xml file was put in the top level, rather than in the config directory.

Action:
Ensure that the config.xml file is in the correct location in the domain.

BEA-141242
Invalid configuration version found at {1} version = {0}.

Category:
Management

Cause:
WebLogic Server found a config.xml file with a version that does not match any known version of the product.

Action:
Ensure that the version string in the config.xml file is valid.

BEA-141243
The property {0} in element {1} has been deprecated in version {2} - {3}.

Category:
Management

Cause:
The config.xml file contained elements that have been deprecated.

Action:
Replace or remove the deprecated configuration artifacts.

BEA-141244
Schema validation errors while parsing {0} - {1}.

Category:
Management

Cause:
The WebLogic Server configuration files are defined by a schema. When parsing these files, they are validated against the schema. This warning indicates that there were problems found during validation. The problems may or may not be fatal, depending on the setting of the system property weblogic.configuration.schemaValidationEnabled.

Action:
See the error details for more information on the validation problem.

BEA-141245
Schema validation error in {0}. See the log for details. Schema validation can be disabled by starting the server with the command line option: {1}.

Category:
Management

Cause:
The WebLogic Server configuration files are defined by a schema. When parsing these files, they are validated against the schema. This warning indicates that there were problems found during validation. The problems may or may not be fatal, depending on the setting of the system property weblogic.configuration.schemaValidationEnabled.

Action:
See the error details for more information on the validation problem.

BEA-141246
The configuration directory {0} does not exist.

Category:
Management

Cause:
The server was booted from a directory that does not contain a configuration directory.

Action:
Ensure that the server is booted from a valid domain directory.

BEA-141247
The configuration directory {0} does not exist, and the Administration Server is not available.

Category:
Management

Cause:
The configuration directory is missing and the Administration Server is not available to download a copy. In this case, the Managed Server cannot boot.

Action:
Ensure that either the server is booted from a valid domain directory or that the Administration Server is available.

BEA-141248
The configuration directory {0} is missing the file {1}.

Category:
Management

Cause:
The server was booted from a directory that does not contain a valid domain configuration.

Action:
Ensure that the server is booted from a valid domain directory.

BEA-141249
The configuration directory {0} is missing the file {1}, and the Administration Server is not available to download it.

Category:
Management

Cause:
The server was booted from a directory that does not contain a valid configuration, and the Administration Server is unavailable to download the current configuration files.

Action:
Ensure that either the server is booted from a valid domain directory or that the Administration Server is available.

BEA-141251
The attribute {1} from the element {0} was introduced in version 9.0.0.0 or later and is not valid in a pre-9.0 config.xml file.

Category:
Management

Cause:
An attribute that was introduced in release 9.0 or later was found in a pre-9.0 config.xml file.

Action:
Verify that the upgrade process correctly handles the named elements by reviewing the upgraded configuration files.

BEA-141252
The domain version {0} is greater than the release version {1} of this server.

Category:
Management

Cause:
The DomainVersion in the configuration used by the Administration Server is not compatible with the release version of this Managed Server.

Action:
Update the WebLogic Server installation for this server.

BEA-141253
An error occurred while loading the configuration translator {0} : {1}.

Category:
Management

Cause:
The message includes the specific cause.

Action:
Repair or remove the configuration translator.

BEA-141254
Generating new domain directory in {0}.

Category:
Management

Cause:
There was no domain directory at the specified location. Either a command line option or user input specified creation of the domain, so generation of the domain is commencing.

Action:
No action is required. The domain directory will be generated, and the server will continue to boot normally.

BEA-141255
Domain generation completed in {0} milliseconds.

Category:
Management

Cause:
A new domain has been generated.

Action:
No action is required. The server will continue to boot normally.

BEA-141256
A RuntimeException occurred while adding or removing a configuration element: {0}.

Category:
Management

Cause:
See the exception text for details.

Action:
The message includes information on the root cause. Review this message to determine the appropriate action.

BEA-141257
An exception occurred while translating a configuration file: {0}.

Category:
Management

Cause:
See the exception text for details.

Action:
The message includes information on the root cause. Review this message to determine the appropriate action.

BEA-141258
An exception occurred while constructing an ObjectName: {0}.

Category:
Management

Cause:
See the exception text for details.

Action:
The message includes information on the root cause. Review this message to determine the appropriate action.

BEA-141259
An exception occurred while sending a Notification: {0}.

Category:
Management

Cause:
See the exception text for details.

Action:
The message includes information on the root cause. Review this message to determine the appropriate action.

BEA-141260
An exception occurred while removing a Notification: {0}.

Category:
Management

Cause:
See the exception text for details.

Action:
The message includes information on the root cause. Review this message to determine the appropriate action.

BEA-141261
An exception occurred while unregistering a Notification: {0}.

Category:
Management

Cause:
See the exception text for details.

Action:
The message includes information on the root cause. Review this message to determine the appropriate action.

BEA-141262
An exception occurred while adding a Filter: {0}.

Category:
Management

Cause:
See the exception text for details.

Action:
The message includes information on the root cause. Review this message to determine the appropriate action.

BEA-141263
An exception occurred in an MBean customizer: {0}.

Category:
Management

Cause:
See the exception text for details.

Action:
The message includes information on the root cause. Review this message to determine the appropriate action.

BEA-141264
An exception occurred in an MBeanProxy: {0}.

Category:
Management

Cause:
See the exception text for details.

Action:
The message includes information on the root cause. Review this message to determine the appropriate action.

BEA-141265
Could not get the configuration lock used to serialize access to the configuration files.

Category:
Management

Cause:
The lock could not be obtained before the specified timeout period had elasped.

Action:
Verify the configuration files and ensure that no server has hung, thereby not releasing the lock.

BEA-141266
Parsing failure in {0}: {1}.

Category:
Management

Cause:
This error occurs when the configuration file has invalid XML syntax or other errors.

Action:
Validate the contents of the configuration file.

BEA-141267
Parsing failure in {0} on line {1}: {2}.

Category:
Management

Cause:
This error occurs when the configuration file has invalid XML syntax or other errors.

Action:
Validate the contents of the configuration file.

BEA-141268
Parsing failure in {0} on line {1}, column {2}: {3}.

Category:
Management

Cause:
This error occurs when the configuration file has invalid XML syntax or other errors.

Action:
Validate the contents of the configuration file.

BEA-141269
The temporary bean tree {0} was allocated for an undo, get, or activate operation, but has not been garbage collected.

Category:
Management

Cause:
The temporary bean tree has not been garbage collected.

Action:
Repeat the specified operation and determine if memory usage in the server is increasing.

BEA-141270
Could not get the configuration lock used to serialize access to configuration files. Retrying for another {0} seconds.

Category:
Management

Cause:
Another server was reading or writing to the configuration files, and the lock could not be obtained before the specified timeout period had elasped.

Action:
No action is required. If the configuration subsystem fails to get the lock, and the number of retries is exhausted, a different message with error severity will be displayed.

BEA-141271
An IOException occurred while recording setAttribute {1} on MBean {0}. Exception: {2}.

Category:
Management

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Take action based upon the provided exception details.

BEA-141272
An IOException occurred while recording invoke {1} on MBean {0}. Exception: {2}.

Category:
Management

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Take action based upon the provided exception details.

BEA-141273
An upgrade framework class was not found. Exception: {0}. The configuration and upgrade framework component may not have been installed.

Category:
Management

Cause:
The configuration and upgrade framwork component may not have been installed.

Action:
Install the Configuration Wizard and pgrade framework component by running the installer again.

BEA-141274
Production mode has been specified at the command line using the the weblogic.ProductionModeEnabled system property. This system property overrides the development mode setting contained in the config.xml file. However, the Administration Console and WLST show the attribute values and defaults that correspond to the development mode specified in the config.xml file.

Category:
Management

Cause:
The command line overrides are not persisted to the config.xml file.

Action:
If the Administration Console or WLST should display production mode defaults for attributes, then enable production mode in the Administration Console or WLST and activate the changes.

BEA-141275
Development mode has been specified at the command line by setting the weblogic.ProductionModeEnabled system property to false. This system property overrides the production mode setting contained in the config.xml file. However, the Administration Console and WLST show the attribute values and defaults that correspond to the production mode specified in the config.xml file.

Category:
Management

Cause:
The command line overrides are not persisted to the config.xml file.

Action:
If the Administration Console or WLST should display development mode defaults for attributes, then enable development mode in the Administration Console or WLST and activate the changes.

BEA-141276
An exception occurred while obtaining the class for interface {0}. The exception is: {1}

Category:
Management

Cause:
A resource or classloader issue caused the class lookup to fail.

Action:
See the underlying exception to troubleshoot further.

BEA-141277
The JMX MBean PlatformMBeanServerUsed attribute is true, but the Platform MBeanServer was created without the hooks for the WebLogic Server security infrastructure. The Platform MBeanServer will not be used and Platform MBeans will not be available using the WebLogic Server Runtime or Domain Runtime MBeanServers. This can occur if Platform MBeanServer system properties or JVM options (-Dcom.sun.management.jmxremote or JRockit -XManagement) were defined. To allow the Platform MBeanServer to be used, either remove the system properties and JVM options or start WebLogic Server with the following system property: -Djavax.management.builder.initial=weblogic.management.jmx.mbeanserver.WLSMBeanServerBuilder To eliminate this log error if Platform MBeans do not need to be available when using WebLogic Server, set the PlatformMBeanUsed attribute in the JMXMBean to false.

Category:
Management

Cause:
A system property was specified that caused the Platform MBeanServer to be created before the WebLogic Server Runtime MBeanServer.

Action:
Remove the system properties or start WebLogic Server with the following system property: -Djavax.management.builder.initial=weblogic.management.jmx.mbeanserver.WLSMBeanServerBuilder.

BEA-141278
Java entropy configuration is: {0}.

Category:
Management

Cause:
This message is informational and is printed every time WebLogic Server starts.

Action:
Change your jave entropy configuration, if needed.

BEA-141279
Detected BLOCKING java entropy configuration. This is the most secure setting, but may cause performance issues on machines with few sources of entropy.

Category:
Management

Cause:
This message is informational and is printed every time WebLogic Server starts.

Action:
Change your jave entropy configuration, if needed.

BEA-141280
Detected NON-BLOCKING java entropy configuration. This setting will provide the best performance on machines with few sources of entropy, but is less secure than a blocking entropy configuration.

Category:
Management

Cause:
This message is informational and is printed every time WebLogic Server starts.

Action:
Change your jave entropy configuration, if needed.

BEA-141281
A ForeignJNDIProvider named {0} has two child ForeignJNDILinks named {1} and {2}, which both have the same LocalJNDIName {3}. This duplication of LocalJNDIName is invalid.

Category:
Management

Cause:
Two links cannot share the same LocalJNDIName because it would be unclear as to which remote JNDI name to link to.

Action:
Change the LocalJNDIName of one of the ForeignJNDILinks.

BEA-141282
Server name {0} not found in domain {1}.

Category:
Management

Cause:
A managed server is started with -Dweblogic.Name with a value that is not configured in the domain.

Action:
Specify the correct value of the param -Dweblogic.Name.

BEA-141283
Server name could not be determined.

Category:
Management

Cause:
Either the name is not specified or the specified name does not exist in the config.xml file.

Action:
Specify the correct value of the -Dweblogic.Name parameter.

BEA-141284
A deprecated MBean for {0} has been removed from the current version of WebLogic Server but still exists in an application configuration file.

Category:
Management

Cause:
A deprecated MBean for {0} has been removed from the current version of WebLogic Server but still exists in an application configuration file.

Action:
Update the configuration file to remove the deprecated MBean.

BEA-141285
The network access point property {0} was ignored because the specified network access point name was not found.

Category:
Management

Cause:
The specified network access point does not exist in the configuration.

Action:
Modify the system property, and specify a valid network access point name.

BEA-141286
The creation of the dynamic server failed with an exception.

Category:
Management

Cause:
An exception occurred during the creation of the dynamic server.

Action:
Take action based upon the provided exception details, make any required changes, and retry the operation.

BEA-141287
No matching machines were found based on the MachineNameMatchPrefix property. No machine has been calculated for servers from dynamic servers {0}.

Category:
Management

Cause:
The MachineNameMatchPrefix did not match any of the existing machines in the domain.

Action:
Set the MachineNameMatchPrefix property so it matches the machine names in the domain.

BEA-141288
Unable to obtain file lock but will retry.

Category:
Management

Cause:
This is an informational message only.

Action:
If WebLogic Server fails to start because it was unable to obtain the file lock, then the lock files need to be removed manually before restarting WebLogic Server.

BEA-141289
Upgrade of 8.1 or prior domains is no longer supported. Convert the {1} from version {0} to 10.x format using weblogic.Upgrade.

Category:
Management

Cause:
WebLogic Server found a config.xml file with a version that is no longer supported.

Action:
Upgrade the config.xml file to a newer version using weblogic.Upgrade from a 10.3 or lower version of the product.

BEA-141290
Configuration plug-in not found for component type "{0}" in location "{1}"

Category:
Management

Cause:
The plug-in JAR file was not found.

Action:
Verify the installation to ensure that the plug-in was installed correctly.

BEA-141291
A system component for component type "{0}" was not defined in config.xml. The file "{1}" will not be distributed to the external server.

Category:
Management

Cause:
The system component is not defined in config.xml

Action:
Define the corresponding system component in config.xml.

BEA-141292
A machine was not specified in the system component "{0}" in config.xml. The file "{1}" will not be distributed to the external server.

Category:
Management

Cause:
The machine for the system component is not defined in config.xml

Action:
Define the corresponding machine in the system component in config.xml.

BEA-141293
Bad CAM replication exclusive file {0} : {1}.

Category:
Management

Cause:
See the error message for details.

Action:
Correct the error in the CAM replication exclusive file.

BEA-141294
Found invalid entries in CAM replication exclusive file {0}: {1}.

Category:
Management

Cause:
There are invalid entries in the file.

Action:
Correct the invalid entries in the file.

BEA-141295
Unable to contact Node Manager on "{1}". Activation for system component "{0}" is deferred until "{1}" becomes available.

Category:
Management

Cause:
Contact with Node Manager on "{1}" could not be made.

Action:
No action is required.

BEA-141296
Unable to contact Node Manager on "{1}". Activation for system component "{0}" is deferred until "{1}" becomes available.

Category:
Management

Cause:
Contact with Node Manager on "{1}" could not be made.

Action:
No action is required.

BEA-141297
Could not get the server file lock. Ensure that another server is not running in the same directory. Retrying for another {0} seconds.

Category:
Management

Cause:
Another server is running and still has the server lock.

Action:
Check to see if another server is running.

BEA-141298
Could not register with the Administration Server: {0}

Category:
Management

Cause:
A network connection failed or an I/O exception occurred.

Action:
Check the underlying exception and determine why the Managed Server could not connect to the Administration Server.

BEA-141299
An exception occurred during the registration of MBeans in the MBeanServer : {0}.

Category:
Management

Cause:
See the exception text for details.

Action:
The message includes information on the root cause. Review the message to determine the appropriate action.

BEA-141300
The activate changes operation for request "{0}" could not be completed because the activate timed out. Detailed state info is: {1}

Category:
Management

Cause:
The activate changes operation timed out.

Action:
Try increasing the activate changes timeout value. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-141301
Access not allowed for ObjectName: {0}, on action: {1}, target {2} in partition {3}.

Category:
Management

Cause:
The user does not have enough access to the MBean in the partition.

Action:
Check WebLogic Server JMX policies to determine which role is required to access MBeans.

BEA-141302
Access not allowed for Subject: {0}, on resource {1}, action: {2}, target {3}.

Category:
Management

Cause:
The Subject role for the user does not have enough access to the MBean.

Action:
Check WebLogic Server JMX policies to determine which role is required to access MBeans.

BEA-141303
The internal method that you have invoked is not available unless you are running as Kernel. You are running as: {0}

Category:
Management

Cause:
The Subject role for the user does not have enough access to the MBean.

Action:
Check WebLogic Server JMX policies to determine which role is required to access MBeans.

BEA-141304
Access not allowed for Subject roles: {0} on ObjectName {1}: Resource Type: {2}, Action: {3}, Target: {4} in partition {5}

Category:
Management

Cause:
The person with the specified Subject role does not have enough access to the MBean.

Action:
Check WebLogic Server JMX policies to determine which role is required to access MBeans.

BEA-141305
An error occurred while firing an edit DomainMBean reload event: {0}

Category:
Management

Cause:
EditAccess fires an event when the edit DomainMBean is reloaded but one listener throws an exception.

Action:
Check the JMX client.

BEA-141306
JMS configuration error --- {0} ---.If you need to delay fixing this problem, you can force a log message to occur instead of a configuration exception by configuring the "{1}" system property to false. This system property will be removed in a future 12.2.1 stage.

Category:
Management

Cause:
JMS resource MBean validations failed.

Action:
Check the cross MBean relationships of JMS resources.

BEA-141307
Unable to connect to the Administration Server. Waiting {1} second(s) to retry (attempt number {0} of {2}).

Category:
Management

Cause:
The Administration Server is not available.

Action:
Start the Administration Server.

BEA-141308
New

Category:
Management

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-141309
Initialized

Category:
Management

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-141310
Prepared

Category:
Management

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-141311
Activated

Category:
Management

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-141312
Suspended

Category:
Management

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-141313
Automatic resolve operation during startEdit fails. {0}

Category:
Management

Cause:
{0}

Action:
It is recommended to call resolve() manually.

BEA-141314
Use of the GlobalMBeansVisibleToPartitions system property is temporary. It serves only as a transitional aid to the new MBean visibility model. This warning is generated when it is detected that the old MBean visibility model is in use. Switch to the new model by eliminating the use of the -DGlobalMBeansVisibleToPartitions property. This property will be removed prior to August 2015.

Category:
Management

Cause:
The system property -DGlobalMBeansVisibleToPartitions=true was included in the server startup command.

Action:
Remove the system property -DGlobalMBeansVisibleToPartitions=true or use -DGlobalMBeansVisibleToPartitions=false when starting the server.

BEA-141315
Canceling the configuration update failed with an exception. {0}

Category:
Management

Cause:
An exception occurred during an attempt to cancel an update. {0}

Action:
Ensure that the config is valid. Take action based upon the provided exception details, make any required changes, and retry the activate.

BEA-141316
An exception was received during the prepare phase of configuration, the system is attempting to recover. {0}

Category:
Management

Cause:
An exception occurred during an attempt to prepare an update. {0}

Action:
If the system is unable to automatically recover, ensure that the config is valid. Take action based upon the provided exception details, make any required changes, and retry the activate.

BEA-141317
Auto-halting partition "{0}" due to config change; no active targeted admin resource groups

Category:
Management

Cause:
This is an informational message.

Action:
No action is required.

BEA-141318
Auto-booting partition "{0}" due to config change; active targeted admin resource groups

Category:
Management

Cause:
This is an informational message.

Action:
No action is required.

BEA-141319
The file distribution servlet failed to initialize JMX default security policies due to the following error: {0}.

Category:
Management

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
No action is required if REST management support is not required. Otherwise, configure an authorization security provider in the security configuration that implements weblogic.security.spi.PolicyConsumer such as the XACML Authorization provider.

BEA-141320
The JMX invocation timed out for request "{0}" for activate changes operation. Detailed state info is: {1}

Category:
Management

Cause:
The JMX invocation timed out for activate changes operation.

Action:
Compare the JMX invocation timeout value and activate timeout values. If using WLST, specify timeout in connect() command. If JMX API is used, specify the value of jmx.remote.x.request.waiting.timeout in the JMX client while creating the JMX connection.

BEA-141321
Property {0} was overrloaded via situational properties to {1}

Category:
Management

Cause:
Situational Properties are in effect. {0} = {1}

Action:
If the property setting is incorrect, update the situational properties file.

BEA-141322
The situational config file has an invalid format, it is being ignored: {0}

Category:
Management

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Update the situational config file.

BEA-141323
The situational config file has an invalid format, it is being ignored: {0} because {1}

Category:
Management

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Update the situational config file.

BEA-141324
Unable to obtain file lock {0} due to {1}, but will retry.

Category:
Management

Cause:
This is an informational message only.

Action:
If WebLogic Server fails to start because it was unable to obtain the file lock, then the lock file needs to be removed manually before restarting WebLogic Server.

BEA-141325
There was an exception while acquiring the configuration lock. The exception was {0}

Category:
Management

Cause:
Refer to the exception information for more details as to the probable cause of this error

Action:
The action taken will depend on the exception that was thrown

BEA-141326
There was an exception while releasing the configuration lock. The exception was {0}

Category:
Management

Cause:
Refer to the exception information for more details as to the probable cause of this error

Action:
The action taken will depend on the exception that was thrown

BEA-141327
The SitConfigRequired configuration element is set to true, but no situational config files were found.

Category:
Management

Cause:
No situational config files were found.

Action:
Either change the SitConfigRequired configuration element for the server to false, or ensure that situational config files are present during startup.

BEA-141328
The non-dynamic attribute {1} on {0} was attempted to be changed via a situational configuration file. This change may require redeploying or rebooting configured entities before it takes effect.

Category:
Management

Cause:
This happens when one or more of the changes made to the configuration via situational configuration files affect non-dynamic settings.

Action:
Restart the server or redeploy the entity to ensure the change takes effect.

BEA-141329
Error loading the situational config files: {0}

Category:
Management

Cause:
Refer to the embedded error message information for more details as to the probable cause of this error.

Action:
Update the situational config file to correct the error.

BEA-141330
Loading situational config file: {0}

Category:
Management

Cause:
This is an informational message.

Action:
No action is required.

BEA-141331
Canceling Edit Lock without discarding or activating the pending changes. Unactivated changes have been saved to the domain directory.

Category:
Management

Cause:
The user has cancelled the edit lock without either activating or undo the saved pending changes. This is not an error, but unactivated changes will impact later in case one performs WLST offline changes.

Action:
Either activate or undo the unactivated changes.

BEA-149000
Unable to create DeployerRuntimeMBean.

Category:
Deployer

Cause:
This may occur if an error at the JMX level exists.

Action:
Report this problem to My Oracle Support.

BEA-149001
No application named "{0}" exists for operation "{1}".

Category:
Deployer

Cause:
The application name was likely misspelled.

Action:
Verify that the application is correctly named.

BEA-149002
The source file was not provided for activation of application: "{0}".

Category:
Deployer

Cause:
Source files do not exist for the application to be deployed.

Action:
Make source files available for the application to be deployed in the said path.

BEA-149003
Unable to access application source information in "{0}" for application "{1}". The specific error is: {2}.

Category:
Deployer

Cause:
Source files for the application to be deployed are not accessible.

Action:
Ensure that no other process is using the source file(s).

BEA-149004
Failures were detected while initiating {1} task for application "{0}".

Category:
Deployer

Cause:
Task creation can fail for many reasons.

Action:
Check the error message and take appropriate action.

BEA-149011
Some of the targets in the deployment request are not configured in this domain. The named targets are: "{0}".

Category:
Deployer

Cause:
This error occurs when a deployment request is made to a target that is not configured.

Action:
Ensure that the target list in the request is correct.

BEA-149013
Application "{0}" does not define the module, "{1}". {2} are the known valid module(s) for this application.

Category:
Deployer

Cause:
Incorrect deployment information was provided in the activate request.

Action:
Ensure that the module information in the request is accurate. If adding modules, ensure that the source file is specified again so that it is reloaded and any new modules are deployed.

BEA-149014
Target "{0}" is not defined.

Category:
Deployer

Cause:
Incorrect deployment information was provided in the activate request.

Action:
Ensure that the target information in the request is accurate.

BEA-149015
Unable to add "{0}" to component "{1}".

Category:
Deployer

Cause:
The component is already targeted to the server, cluster, or virtual host.

Action:
Check the target list.

BEA-149021
Rejecting {2} request for application "{1}". The specified ID, {0}, is already being used.

Category:
Deployer

Cause:
A {1} request included an ID provided by a user that is already assigned to another task.

Action:
Choose a different ID or allow the system to allocate an ID for the request.

BEA-149025
An invalid attempt was made to target a non-Web application component, "{1}", in application "{0}" to a virtual host, "{2}".

Category:
Deployer

Cause:
An invalid attempt was made to target a non-Web application to virtual hosts.

Action:
Correct the target list.

BEA-149026
{2} application {0} on {1}.

Category:
Deployer

Cause:
This is an informational message about the task description.

Action:
This is an informational message about the task description.

BEA-149027
Unable to activate the application "{1}" from source "{0}". Reason: {2}

Category:
Deployer

Cause:
The application was improperly defined.

Action:
Define the application properly.

BEA-149028
An invalid path, "{1}", was specified for the application "{0}".

Category:
Deployer

Cause:
The configured path for this application does not exist.

Action:
Provide the application files in the specified location.

BEA-149031
The staging mode of "{0}" is invalid. The legal values are "stage" or "nostage".

Category:
Deployer

Cause:
An invalid staging mode has been specified.

Action:
Specify a valid staging mode for the deployment request.

BEA-149032
An attempt to restart a task has been rejected. The task has already been started.

Category:
Deployer

Cause:
This error results if start is called on a task that has already been started.

Action:
Do not call start on a task that has already been started.

BEA-149033
{2} application {0} on {1}.

Category:
Deployer

Cause:
An application-level deployment notification has been reported.

Action:
No action is required. This is an informational log message.

BEA-149034
An exception occurred for task {0}: {1}.

Category:
Deployer

Cause:
An error occurred while reporting the application status.

Action:
The error may be due to server instability. Check the health of the server.

BEA-149035
Module {0} reported error: {1}.

Category:
Deployer

Cause:
The deployment request failed.

Action:
Check the exception log and take appropriate action.

BEA-149038
Initiating task for {1} : {0}.

Category:
Deployer

Cause:
This is an informational message.

Action:
No action is required.

BEA-149040
An attempt to change the staging mode for the application "{0}" has been rejected.

Category:
Deployer

Cause:
An attempt was made to change the staging mode for the application.

Action:
The staging mode cannot be changed once it is set. Try deploying again without changing the staging mode.

BEA-149045
An attempt to add cluster target "{0}" was rejected, since cluster member "{1}" is also targeted by module "{2}". Targeting to a cluster member results in different behaviors than targeting to the entire cluster.

Category:
Deployer

Cause:
A cluster member is already in the target list of the module.

Action:
Remove the cluster member from the target list, or re-target the cluster member rather than the cluster itself.

BEA-149048
An attempt to add server target "{1}" to module "{2}" has been rejected. This is because its parent cluster, "{0}", is also targeted by the module.

Category:
Deployer

Cause:
The module is already targeted to a cluster that contains the server.

Action:
Remove the cluster from the target list or remove the cluster member from the target list.

BEA-149054
An attempt to add a virtual host target "{0}" to a non-Web application module "{1}" has been rejected.

Category:
Deployer

Cause:
An EJB or connector was attempting to target a virtual host.

Action:
Remove the host from target list.

BEA-149055
Adding server {1} of cluster {0} as a target for module {3}. This module also includes server {2} that belongs to this cluster as one of its additional targets. Having multiple individual servers of a cluster as targets instead of having the entire cluster as the target can result in non-optimal load balancing and scalability. Therefore, this is not usually recommended.

Category:
Deployer

Cause:
The module is already targeted to a different cluster member.

Action:
Target the entire cluster to the module.

BEA-149058
Distribute can only have stage as its staging mode. Application "{0}" has {1} as its staging mode.

Category:
Deployer

Cause:
This is an unexpected error.

Action:
Specify a valid staging name.

BEA-149059
Module {1} of application {0} is transitioning from {2} to {3} on server {4}.

Category:
Deployer

Cause:
A module is being deployed.

Action:
No action is required.

BEA-149060
Module {1} of application {0} successfully transitioned from {2} to {3} on server {4}.

Category:
Deployer

Cause:
A module is being deployed.

Action:
No action is required.

BEA-149061
Module {1} of application {0} failed to transition from {2} to {3} on server {4}.

Category:
Deployer

Cause:
An error was encountered during a module deployment.

Action:
Details of the specific failure are documented in the associated log entries. Take appropriate action.

BEA-149062
The task containing ID {0} cannot be canceled, since it has already completed execution.

Category:
Deployer

Cause:
An attempt has been made to cancel a deployment task that has completed execution.

Action:
Do not attempt this operation on a completed task.

BEA-149066
Unable to deploy application "{0}", because module "{1}" does not provide a valid URI.

Category:
Deployer

Cause:
The application is incorrectly configured.

Action:
Provide a URI for the module, or remove the application from the configuration.

BEA-149068
This is an unexpected exception.

Category:
Deployer

Cause:
An unexpected exception occurred.

Action:
No action is required.

BEA-149069
Deploying {0} using a deprecated protocol.

Category:
Deployer

Cause:
The application is configured with TwoPhase=false or is not a recognized type of application. For example, an application that is not an EAR file (no application.xml) but has multiple modules will not be deployed with the two-phase protocol.

Action:
No action is required.

BEA-149073
The application "{0}" has no configured modules.

Category:
Deployer

Cause:
The application is improperly configured.

Action:
The application will be marked as undeployable. After resolving configuration issues with the application, the administrator can retry the deployment.

BEA-149074
Successfully completed deployment task: {0}.

Category:
Deployer

Cause:
A deployment operation was requested.

Action:
No action is required.

BEA-149078
Stack trace for message {0}

Category:
Deployer

Cause:
A deployment failure occurred.

Action:
No action is required.

BEA-149080
A partial update of an archived application is not allowed. Application "{0}" cannot be redeployed.

Category:
Deployer

Cause:
There was an attempt to partially redeploy an archived application.

Action:
Try deploying the entire application.

BEA-149081
Cannot {2} application, "{0}", with version "{1}". The application was previously deployed without a version.

Category:
Deployer

Cause:
An attempt was made to {2} a versioned application when it was previously deployed without a version.

Action:
Try {2} without a version.

BEA-149082
Cannot {2} application "{0}" without a version. The application was previously deployed with version "{1}".

Category:
Deployer

Cause:
An attempt was made to {2} an application without a version when it was previously deployed with a version.

Action:
Try {2} with a version.

BEA-149083
An attempt was made to activate the application "{0}" when stop was in progress.

Category:
Deployer

Cause:
An attempt was made to activate the application "{0}" when stop was in progress.

Action:
Try to activate the application "{0}" again after the stop is done. If it is a graceful stop, stop the application forcefully to end the graceful stop immediately.

BEA-149085
No application version was specified for application "{0}". The {2} operation will be performed against the currently active version "{1}".

Category:
Deployer

Cause:
No application version was specified for the operation.

Action:
Verify that the currently active version is the desired version for the operation. If not, perform the operation again with the -app_version operation to specify a particular version.

BEA-149086
The application {0} is being retired gracefully.

Category:
Deployer

Cause:
This is an informational message.

Action:
No action is required.

BEA-149087
The application {0} will be retired after {1} seconds.

Category:
Deployer

Cause:
This is an informational message.

Action:
No action is required.

BEA-149088
The retirement for application {0}, which was scheduled to happen after {1} seconds, is canceled.

Category:
Deployer

Cause:
This is an informational message.

Action:
No action is required.

BEA-149089
An attempt was made to activate the application "{0}" when retirement was in progress.

Category:
Deployer

Cause:
An attempt was made to activate the application "{0}" when retirement was in progress.

Action:
Try to activate the application "{0}" again after the retirement is done. If it is a graceful retirement, undeploy the application to end the graceful retirement immediately.

BEA-149091
An attempt was made to deploy application "{0}" with specified archive version "{1}". However, the application archive, as specified in the source, has version "{2}".

Category:
Deployer

Cause:
This error occurs when an attempt is made to specify a version that is different from the manifest version of the application archive in the source location.

Action:
Perform the deployment again without specifying the version, or specify version "{2}" instead of "{1}".

BEA-149092
The source is not specified for the deployment operation of application "{0}", and the expected version is "{1}". However, the application archive at the source location for a previous deployment of version "{1}" now has version "{2}".

Category:
Deployer

Cause:
The source is not specified for the deployment operation of application "{0}", and the expected version is either explicitly specified or the currently active version. However, the application archive at the previously configured source location of the expected version has a different manifest version.

Action:
Perform deployment again specifying either the source location or version "{2}".

BEA-149093
No version specified for the versioned application named "{0}" for operation {1}, and no active version is available.

Category:
Deployer

Cause:
The version was not specified for the operation when no currently active version was available.

Action:
Specify the version of the application for the operation.

BEA-149095
The application {0} is being retired now.

Category:
Deployer

Cause:
This is an informational message.

Action:
No action is required.

BEA-149096
Operation {1} is deprecated and cannot be applied to versioned application "{0}". Use operation {2} instead.

Category:
Deployer

Cause:
An attempt was made to perform the deprecated operation {1} on a versioned application. Use operation {2} instead.

Action:
Use operation {2} instead.

BEA-149097
The retirement for application "{0}" failed.

Category:
Deployer

Cause:
This may have happened due to a problem with accessing the persistent store.

Action:
Check for other log messages that give more information about the failure.

BEA-149098
An attempt was made to gracefully undeploy the application "{0}" when retirement was in progress.

Category:
Deployer

Cause:
An attempt was made to gracefully undeploy the application "{0}" when retirement was in progress.

Action:
To stop the graceful retirement, force the application to undeploy.

BEA-149099
Unexpected errors occurred while sending deployment event {1} on behalf of application "{0}".

Category:
Deployer

Cause:
Deployment event listeners that are registered to receive a deployment event generated unexpected exceptions when processing the deployment event {1} on behalf of application "{0}".

Action:
Report this problem to My Oracle Support.

BEA-149100
Unexpected errors occurred while sending a vetoable deployment event on behalf of application "{0}".

Category:
Deployer

Cause:
Deployment event listeners registered to receive a vetoable deployment event generated unexpected exceptions when processing the deployment event {1} on behalf of application "{0}".

Action:
Report this problem to My Oracle Support.

BEA-149101
Application "{0}" is not deployed on target "{1}". Therefore, it cannot be undeployed or removed. The requested operation {2} is valid only on the deployed targets of the application.

Category:
Deployer

Cause:
Incorrect target information was provided in the {2} operation request.

Action:
Ensure that the target information in the request is accurate.

BEA-149102
Production redeployment is not supported for application "{0}", which is of module type {1}. Production redeployment is supported for the following module types only: {2}. If not attempting to perform production redeployment, try deploying without a version.

Category:
Deployer

Cause:
Attempt was made to perform production redeployment for an unsupported module type.

Action:
Ensure that the module type is supported before performing production redeployment. Or, try deploying again without a version.

BEA-149103
An exception occurred while executing task {0} for application "{1}": {2}.

Category:
Deployer

Cause:
An exception occurred while executing the deployment task for the application.

Action:
If it is an application error, correct it if possible. If it is a system error, contact My Oracle Support.

BEA-149104
Update request for "{0}" does not specify any descriptors to be updated

Category:
Deployer

Cause:
The deployment plan does not include any module overrides.

Action:
Ensure that the deployment plan is properly constructed.

BEA-149105
An attempt was made to deploy a library located at "{2}" with name "{0}", which is different from the one specified in the manifest of the library: "{1}".

Category:
Deployer

Cause:
This error occurs when an attempt is made to specify a name that is different from the one in the manifest of the library in the source location.

Action:
Perform deployment again without specifying the name of the library.

BEA-149106
An attempt was made to deploy a library located at "{0}" without specifying a name, and the library does not have "Extension-Name" specified in its manifest.

Category:
Deployer

Cause:
This error occurs when an attempt is made to deploy a library without specifying a name, and the library module does not have "Extension-Name" specified in its manifest.

Action:
Perform deployment again specifying the name of the library either during deployment or in the manifest of the library, using the "Extension-Name" attribute.

BEA-149107
An attempt was made to deploy library "{0}" with specified specification version "{1}" and implementation version "{2}". However, the library manifest has specification version "{3}" and implementation version "{4}".

Category:
Deployer

Cause:
This error occurs when an attempt is made to specify a version that is different from the manifest version of the library.

Action:
Perform deployment again without specifying the version or after specifying the same version as specified in the manifest.

BEA-149108
Failures were detected while initiating {0} task.

Category:
Deployer

Cause:
Task creation can fail for many reasons.

Action:
Check the error message and take appropriate action.

BEA-149110
An exception occurred while processing the completion of the task {0}, {1}. The active application version state may not have been updated.

Category:
Deployer

Cause:
The deployment subsystem was unable to complete the persistence of the active application version state.

Action:
Check for other log messages that give more information about the failure.

BEA-149111
Application "{0}" is non-versioned, and an attempt was made to redeploy application "{0}" with the source. Redeploying with the source is only allowed when redeploying a new version of a versioned application. Try redeploying again without specifying the source.

Category:
Deployer

Cause:
An attempt was made to redeploy with the source specified for a non-versioned application "{0}". Redeploy again without specifying the source.

Action:
Try redeploying again without specifying the source.

BEA-149112
Application "{0}" is already deployed, and the attempt was made to redeploy application "{0}" again with source. Redeploying with the source is only allowed when redeploying a new version of the application. Try redeploying again without specifying the source or with a new version.

Category:
Deployer

Cause:
An attempt was made to redeploy with the source specified for application "{0}", but application "{0}" was already deployed. Redeploy again without specifying the source or with a new version.

Action:
Try redeploying again without specifying the source or redeploy with a new version.

BEA-149113
Cannot deploy or redeploy application "{0}" because the maximum number of application versions ({2}) for application "{1}" has been exceeded. Currently deployed versions are: "{3}".

Category:
Deployer

Cause:
An attempt was made to deploy or redeploy application "{0}" when the maximum number of application versions ("{2}") for application "{1}" has been exceeded.

Action:
Try undeploying the existing application version(s) before deploying or redeploying the new version(s).

BEA-149114
Cannot deploy or redeploy application "{0}" with version identifier "{1}" because the maximum length of the version identifier ({2}) has been exceeded.

Category:
Deployer

Cause:
An attempt was made to deploy or redeploy application "{0}" with version identifier "{1}" that exceeded the maximum length ({2}).

Action:
Try reducing the version identifier length when deploying or redeploying the application version.

BEA-149115
Cannot deploy or redeploy application "{0}" with invalid version identifier "{1}". Version identifiers may only contain alphanumerics, period, underscore, and hyphen and must be less than 215 characters in length.

Category:
Deployer

Cause:
An attempt was made to deploy or redeploy application "{0}" with invalid version identifier "{1}".

Action:
Try changing the version identifier to a valid one when deploying or redeploying the application version. Version identifiers can only consist of alphanumeric, period, underscore, or hyphen characters and must not be "." or "..".

BEA-149116
Cannot obtain the deployment configuration.

Category:
Deployer

Cause:
The deployment configuration could not be obtained.

Action:
Check for other log messages that give more information about the failure.

BEA-149117
{2} library {0} on {1}.

Category:
Deployer

Cause:
This is an informational message about the task description.

Action:
This is an informational message about the task description.

BEA-149118
"{1}" is not targeted to "{0}".

Category:
Deployer

Cause:
An attempt was made to undeploy the application from a target where it is not deployed.

Action:
Correct the target list for the operation.

BEA-149119
Different targets cannot be specified when deploying a new version "{1}" of application "{0}". The targets specified, "{3}", are different from those of the previous version, "{2}".

Category:
Deployer

Cause:
An attempt was made to deploy a new application version with targets that are different from that of the previous version.

Action:
Try deploying again without specifying targets, or specify the exact same target as the previous version.

BEA-149120
The plan version "{1}" cannot be specified when deploying a non-versioned application "{0}".

Category:
Deployer

Cause:
An attempt was made to deploy a non-versioned application with a plan version.

Action:
Try deploying again with an application version or without the plan version.

BEA-149121
Rejecting {1} request for application {0} because the deployment service is not started.

Category:
Deployer

Cause:
A deployment operation was attempted when the server was starting or shutting down.

Action:
Perform the deployment operation again after the server has started or before the server has shut down.

BEA-149122
Deployment perations on internal application "{0}" are not permitted;.

Category:
Deployer

Cause:
Deployment operations are not permitted on internal applications.

Action:
Do not attempt any deployment operations on internal applications.

BEA-149123
The application "{0}" currently has security model "{1}", and an attempt was made to redeploy the application again with a different security model "{2}". The specified security model will be ignored for the current deployment operation. To change the security model, undeploy the application and deploy it again with the new security model.

Category:
Deployer

Cause:
An attempt was made to redeploy the same application with a different security model.

Action:
Undeploy the application and deploy it again with the new security model.

BEA-149124
Failures were detected while initiating {1} task for application "{0}". Error is: "{2}"

Category:
Deployer

Cause:
Task creation can fail for many reasons.

Action:
Check the error message and take appropriate action.

BEA-149125
No application version was specified for the {0} operation of application "{1}". The {0} operation will be performed against the retired application version "{2}".

Category:
Deployer

Cause:
This is an informational message only.

Action:
No action is required.

BEA-149126
No application version was specified for the {0} operation of application "{1}". The application version "{2}" will not be removed as its retirement is still in progress. Oracle recommends that the application version "{2}" be undeployed explicitly after the retirement is done. An explicit undeploy of the application version can also be performed before retirement is done; however, exercise caution as this may interrupt inflight work.

Category:
Deployer

Cause:
No application version was specified for the {0} operation of application "{1}".

Action:
No action is required.

BEA-149127
Failures were detected while initiating "{0}" task. Error is: "{1}"

Category:
Deployer

Cause:
Task creation can fail for many reasons.

Action:
Check the error message and take appropriate actions.

BEA-149128
The "{1}" option was specified for the {0} operation of application "{2}". The {0} operation will be performed against the retired application version "{3}".

Category:
Deployer

Cause:
This is an informational message only.

Action:
No action is required.

BEA-149129
The "{1}" option was specified for the {0} operation of application "{2}". The {0} operation will be performed against the retiring application version "{3}". Note that retirement is still in progress for version "{3}" and any inflight work will be interrupted.

Category:
Deployer

Cause:
This is an informational message only.

Action:
No action is required.

BEA-149130
The "{1}" option was specified for the {0} operation of application "{2}". The {0} operation will be performed against the currently active version "{3}".

Category:
Deployer

Cause:
This is an informational message only.

Action:
No action is required.

BEA-149131
Cannot perform operation {2} because application "{0}" is in state {1}

Category:
Deployer

Cause:
The application is no longer active.

Action:
Ensure that the application is active. Deploy again if needed.

BEA-149132
Split directory application {0} can only be deployed on the Administration Server.

Category:
Deployer

Cause:
An attempt was made to perform the deployment operation on the split directory application on a server other than the Administration Server.

Action:
For split directory application {0}, perform deployment operations on the Administration Server alone.

BEA-149133
Auto-deployed application {0} can only be deployed on the Administration Server.

Category:
Deployer

Cause:
An attempt was made to perform the deployment operation on the auto-deployed application on a server other than the Administration Server.

Action:
For auto-deployed application {0}, perform deployment operations on the Administration Server alone.

BEA-149134
A redeploy was performed without specifying -source for the archived versioned application "{0}". Partial update of an archived application is not allowed. To perform production redeployment of versioned applications, specify -source with the redeploy operation.

Category:
Deployer

Cause:
An attempt was made to partially redeploy an archived application.

Action:
Specify -source for production redeployment, or redeploy the entire application.

BEA-149135
Operation {2} cannot be performed since application "{0}" is not deployed on the target "{1}".

Category:
Deployer

Cause:
Operation {2} could not be performed because the application was not deployed on the provided target.

Action:
Rery with a valid target.

BEA-149137
{0} is an invalid path for partial redeployment. The URI of the file or directory to be redeployed should be relative to {1}, the root of the enterprise application, or to the standalone module being redeployed.

Category:
Deployer

Cause:
The file could not be located in the application.

Action:
Use a valid specification for the file.

BEA-149138
A subset of the originally configured targets for the application "{0}" was specified. This can potentially lead to out-of-sync applications between the different server targets. The targets specified, "{2}", are different from those of the previous version, "{1}".

Category:
Deployer

Cause:
A deployment operation was performed on an existing application with a subset of the originally configured targets.

Action:
If the application content has changed since the last operation, Ensure that all configured targets are updated. To do so, repeat the operation without specifying targets in order to automatically use the configured targets.

BEA-149139
Application "{0}" is targeted to cluster "{1}", and provided the target for {3} operation is "{2}". The {3} operation on a subset of the targeted clustered servers is not supported.

Category:
Deployer

Cause:
The {3} operation was attempted on one or more servers in the targeted cluster.

Action:
Retry with the targeted cluster, or undeploy from the cluster and deploy to the desired individual servers.

BEA-149140
The task cannot be processed further until the current edit session is activated. When this occurs, task processing will continue. The user can exit the deployer tool without affecting the task.

Category:
Deployer

Cause:
The user is the current owner of the domain configuration edit lock.

Action:
Activate (or cancel) the edit session. The user can exit the deployer tool without affecting the task.

BEA-149141
The AppDeploymentMBean already exists for application "{0}".

Category:
Deployer

Cause:
The AppDeploymentMBean already exists for application "{0}".

Action:
Ensure that different applications do not have the same name.

BEA-149142
Cluster target "{0}" is configured with no servers, and therefore configuration is updated.

Category:
Deployer

Cause:
A deployment to a cluster target was attempted, but the cluster contains no servers.

Action:
No action is required.

BEA-149143
Submodule targets in an application must be specified with the correct module name.

Category:
Deployer

Cause:
A submodule target was specified incorrectly.

Action:
Ensure that the submodule target was specified with the correct syntax and with the correct module name.

BEA-149145
Unable to contact "{0}". Deployment is deferred until "{0}" becomes available. WARNING: If this is a redeploy app and contains JSP pages that have been touched, these JSP changes won't be reflected when the server starts unless precompile is set to true in weblogic.xml

Category:
Deployer

Cause:
Contact with "{0}" could not be made. Deployment is deferred until "{0}" becomes available.

Action:
No action is necessary.

BEA-149146
Attempt to reach the Administration Server with alternate URL: "{0}" failed.

Category:
Deployer

Cause:
The attempt to reach the Administration Server with the alternate URL: "{0}" failed.

Action:
See the exception cause and check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149147
Could not reach the Administration Server through any of its URLs: "{0}".

Category:
Deployer

Cause:
The Administration Server could not be reached through any of its URLs: "{0}".

Action:
See the exception cause and check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149148
Exception occurred while receiving a message on loopback.

Category:
Deployer

Cause:
An exception occurred while receiving a message on loopback.

Action:
See the exception cause and check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149149
Malformed URL: "{0}".

Category:
Deployer

Cause:
The URL: "{0}" was malformed.

Action:
See the exception cause and check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149150
An IOException occurred while reading the input.

Category:
Deployer

Cause:
An IOException occurred while reading the input.

Action:
See the exception cause and check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149151
Could not find a registered DeploymentReceiver to handle requests for "{0}".

Category:
Deployer

Cause:
A registered DeploymentReceiver could not be found to handle requests for "{0}".

Action:
Check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149152
No deployment request for which to set up the context.

Category:
Deployer

Cause:
No deployment request for which to set up the context.

Action:
Check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149153
A "prepare" message was received for ID "{0}" that has already been completed or canceled.

Category:
Deployer

Cause:
A "prepare" message was received for ID "{0}" that has already been completed or canceled.

Action:
Check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149154
A "get deployments response" message was received for ID "{0}" that has no request. It may have already been completed or may have been canceled.

Category:
Deployer

Cause:
A "get deployments response" message was received for ID "{0}" that has no request. It may have already been completed or may have been canceled.

Action:
Check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149155
Received "get deployments response" message "{0}" while already handling one. Ignoring the second request.

Category:
Deployer

Cause:
A "get deployments response" message "{0}" was received while another was being handled. The second request was ignored.

Action:
Check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149156
Illegal state for operation start: "{0}".

Category:
Deployer

Cause:
The start operation was called on an application that either had an update pending or was used with the administration mode flag.

Action:
To move the application from active to administration mode, use the stop operation.

BEA-149157
There is nothing to do for task "{0}".

Category:
Deployer

Cause:
There is nothing to do for task "{0}".

Action:
No action is required.

BEA-149158
No application files exist at "{0}".

Category:
Deployer

Cause:
No application files exist at "{0}".

Action:
No action is required.

BEA-149159
There was an attempt to create a staging directory that is null.

Category:
Deployer

Cause:
There was an attempt to create a staging directory that is null.

Action:
Ensure that the staging directory is properly configured. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149160
There was an attempt to create a staging directory for a null application name.

Category:
Deployer

Cause:
There was an attempt to create a staging directory for a null application name.

Action:
Ensure that the application name is properly configured. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149161
This operation requires that a target be specified.

Category:
Deployer

Cause:
This operation requires that a target be specified.

Action:
Ensure that the deployment request is complete and contains the required targeting information.

BEA-149162
This operation requires that a deployment plan be specified.

Category:
Deployer

Cause:
This operation requires that a deployment plan be specified.

Action:
Ensure that the deployment request is complete and contains the required deployment plan information.

BEA-149163
The domain edit lock is owned by another session in non-exclusive mode. This deployment operation requires exclusive access to the edit lock and therefore cannot proceed. If using "Automatically Aquire Lock and Activate Changes" in the Administration Console, then the lock will expire shortly, so retry this operation.

Category:
Deployer

Cause:
The domain edit lock is owned by another session in non-exclusive mode. This deployment operation requires exclusive access to the edit lock and therefore cannot proceed.

Action:
Ensure that the domain edit lock is available, and try again. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149164
The domain edit lock is owned by another session in exclusive mode. Therefore, this deployment operation cannot proceed.

Category:
Deployer

Cause:
The domain edit lock is owned by another session in exclusive mode. Therefore, this deployment operation cannot proceed.

Action:
Ensure that the domain edit lock is available, and try again. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149165
Invalid target specified.

Category:
Deployer

Cause:
An invalid target was specified.

Action:
See the exception cause and check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149166
Deployments cannot be triggered through configuration updates and through the Deployment APIs simultaneously.

Category:
Deployer

Cause:
Deployments cannot be triggered through configuration updates and through the Deployment APIs simultaneously.

Action:
Ensure that the domain edit lock is available, and try again. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149167
No action was needed to commit the request for "{0}" on "{1}".

Category:
Deployer

Cause:
No action was needed to commit the request for "{0}" on "{1}".

Action:
No action is required.

BEA-149168
Request "{0}" has already been completed or was canceled.

Category:
Deployer

Cause:
The request "{0}" has already been completed or was canceled.

Action:
Check the preceding conflict start message in the logs. Try to avoid the conflict by following one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149169
Requires server restart for completion.

Category:
Deployer

Cause:
In order to complete the action, the server must be restarted.

Action:
Restart the required servers.

BEA-149170
Invalid targeting was specified for this operation. Module and submodule targets cannot both be specified for this type of request.

Category:
Deployer

Cause:
The operation specified both module and submodule targeting, which is invalid for this operation.

Action:
Perform the operation separately for both module and submodule targets.

BEA-149171
Deferred deployment task: {0}

Category:
Deployer

Cause:
A deployment operation was requested with targets that were unreachable.

Action:
No action is required.

BEA-149172
Deployment request {0} is affecting the system resource {1}, which involves a non-dynamic property {2} in {3}. Therefore, a restart of the resource or the appropriate server targets is required for the changes to be active.

Category:
Deployer

Cause:
This is an informational message indicating that deployment involves a non-dynamic property.

Action:
No action is required.

BEA-149178
Application "{0}" is targeted to cluster "{1}", and the provided target for {3} operation is "{2}". This can potentially lead to client request problems on the cluster.

Category:
Deployer

Cause:
An operation was performed on a subset of a cluster for an application targeted to the cluster.

Action:
Ensure that the cluster properly serves requests by performing operations on the cluster rather then on individual servers within the cluster.

BEA-149181
Deployment service encountered an error while aborting the edit session before start. Initiator for this edit session is "{0}". Error is "{1}".

Category:
Deployer

Cause:
See the reported error.

Action:
Take appropriate action based on the reported error.

BEA-149182
An invalid alternate descriptor was specified for the redeploy operation. Alternate descriptors cannot be changed during a redeploy operation.

Category:
Deployer

Cause:
An invalid alternate descriptor was specified for the redeploy operation. Alternate descriptors cannot be changed during a redeploy operation.

Action:
Repeat the redeploy operation without the alternate descriptor.

BEA-149183
An invalid retiretimeout option was specified for the deploy operation. The retiretimeout option was specified as "{2}" for the initial deployment of application "{0}". Retirement policies must be set during the deploy or redeploy of the next version in order to apply to version "{1}" of "{0}".

Category:
Deployer

Cause:
An invalid retiretimeout option was specified for the deploy operation.

Action:
Specify the retiretimeout option during the deploy or redeploy of subsequent versions in order for the retirement to occur correctly at that time.

BEA-149184
The application "{0}" was autodeployed and may only be redeployed by touching the REDEPLOY file in the domain autodeploy directory for the respected application.

Category:
Deployer

Cause:
Autodeployed applications cannot be redeployed through tools.

Action:
See the WebLogic Server documentation on autodeployed applications for more information.

BEA-149185
The application "{0}" was autodeployed and may only be deleted by removing the files from the domain autodeploy directory.

Category:
Deployer

Cause:
Autodeployed application cannot be undeployed through tools.

Action:
See the WebLogic Server documentation on autodeployed applications for more information.

BEA-149186
The application "{0}" was autodeployed and cannot be redistributed.

Category:
Deployer

Cause:
Autodeployed application cannot be redistributed.

Action:
See the WebLogic Server documentation on autodeployed applications for more information.

BEA-149187
An unexpected error occurred when specifying configuration information for the application "{0}" due to {1}.

Category:
Deployer

Cause:
Application configuration upgrade requires targeting information.

Action:
Inspect the problematic application parts and deploy the application.

BEA-149188
No application named "{0}" exists for operation {1}. Operation cannot be performed until the server is restarted.

Category:
Deployer

Cause:
The application was created after non-dynamic changes were activated. The server needed to be restarted.

Action:
Restart the server and then start the application. In the future, start the application before making non-dynamic changes to the configuration.

BEA-149189
An attempt was made to execute the "{0}" operation on an application named "{1}" that is not currently available. The application may have been created after non-dynamic configuration changes were activated. If so, the operation cannot be performed until the server is restarted so that the application will be available.

Category:
Deployer

Cause:
The application may have been created after non-dynamic changes were activated. The server needed to be restarted.

Action:
Restart the server and then perform the operation on the application.

BEA-149190
Changes are pending from another session whose lock has expired. This deployment operation will not activate changes from another edit session and therefore cannot proceed. Either cancel the edit lock or activate the pending changes using the Administration Console or WLST.

Category:
Deployer

Cause:
Changes were made with an edit session that has now expired.

Action:
Cancel the edit lock or activate the pending changes using the Administration Console or WebLogic Scripting Tool (WLST).

BEA-149191
Operation "{0}" on application "{1}" is initializing on "{2}".

Category:
Deployer

Cause:
This is an informational message indicating deployment status change.

Action:
No action is required.

BEA-149192
Operation "{0}" on application "{1}" is in progress on "{2}".

Category:
Deployer

Cause:
This is an informational message indicating deployment status change.

Action:
No action is required.

BEA-149193
Operation "{0}" on application "{1}" has failed on "{2}".

Category:
Deployer

Cause:
This is an informational message indicating deployment status change.

Action:
No action is required.

BEA-149194
Operation "{0}" on application "{1}" has succeeded on "{2}".

Category:
Deployer

Cause:
This is an informational message indicating deployment status change.

Action:
No action is required.

BEA-149195
Operation "{0}" on application "{1}" has been deferred since "{2}" is unavailable.

Category:
Deployer

Cause:
This is an informational message indicating deployment status change.

Action:
No action is required.

BEA-149196
Rejecting {1} request for application {0} because {2} request is running for the application.

Category:
Deployer

Cause:
A second operation for an application was requested when an operation for the application was runnning.

Action:
Perform the operation again when the operation that is running is completed.

BEA-149197
Cannot perform operation {3} because application "{0}" is in state {1} and "{2}" is running.

Category:
Deployer

Cause:
The application is in the wrong state for the operation.

Action:
Ensure that the application is in the correct state before attempting the operation.

BEA-149198
Cannot rename directory "{0}" to {1}.

Category:
Deployer

Cause:
The rename operation failed since the source directory is not present or there is a privilege issue.

Action:
Check that the source directory is present and has the required permissions.

BEA-149199
Security permissions declared in the "{0}" deployment descriptor are not allowed due to the server''s configuration.

Category:
Deployer

Cause:
The server is configured not to allow Java security permissions to be declared in the Weblogic deployment descriptors.

Action:
Remove Java security permissions from the deployment descriptor before re-deployment.

BEA-149202
Encountered an exception while attempting to commit the {0} task for the application "{1}" on [partition-name: {2}].

Category:
Deployer

Cause:
The cause of this error is likely in the application or the application subsystem for that application type.

Action:
Review the exception and attempt to repair the application level. Then re-initiate the deployment request.

BEA-149205
Failed to initialize the application "{0}" due to error {1}

Category:
Deployer

Cause:
The cause of this error is likely in the application or the application subsystem for that application type.

Action:
Review the exception and attempt to repair the application level. Then reinitiate the deployment request.

BEA-149209
The Slave Deployer is resuming.

Category:
Deployer

Cause:
This is an informational message.

Action:
No action is required.

BEA-149229
Server "{0}" in cluster "{1}" is unable to initialize due to failed deployments.

Category:
Deployer

Cause:
This problem occurred due to failed deployments, which are already logged.

Action:
Correct the deployment problem, and restart the server in the cluster.

BEA-149231
Unable to set the activation state to {1} for the application "{0}".

Category:
Deployer

Cause:
An unexpected error occurred.

Action:
Report this error to My Oracle Support.

BEA-149233
An unexpected error occurred during the deployment process.

Category:
Deployer

Cause:
There was a problem with the internal implementation that was not anticipated.

Action:
Report the error and any useful information needed to reproduce the problem to My Oracle Support.

BEA-149239
Application deployment failures were detected during startup of the Administration Server, "{0}", member of cluster "{1}".

Category:
Deployer

Cause:
One or more applications could not be deployed during the startup of the Administration Server.

Action:
Oracle recommends that the Administration Server not be part of a cluster. One response to this warning is to remove it from the cluster and restart the Administration Server. Alternatively, review the Administration Server log to understand why the deployment failed, fix the problem, and redeploy the application.

BEA-149243
The internal application "{0}" could not be deployed. An attempt will be made to retry deploying this application after synchronizing the application files again.

Category:
Deployer

Cause:
It is likely that the internal staged directory was corrupt or there was a failure when deploying the staged application.

Action:
No action is necessary if the retry succeeds. Otherwise, the nature of the failure should provide an indication of the problem and its resolution. If this is not clear, contact My Oracle Support with the relevant logs and configuration files.

BEA-149245
The deployment plan at "{0}" for application "{1}" does not define a valid deployment plan.

Category:
Deployer

Cause:
The application is configured with an incorrect deployment plan document.

Action:
Deploy the application using a valid deployment plan.

BEA-149246
The security realm "{0}" does not support application versioning. Deployment of application "{1}" failed.

Category:
Deployer

Cause:
The security realm "{0}" does not support application versioning. The deployment of the application version failed.

Action:
Deploy the application using a security realm that supports application versioning.

BEA-149247
Failed to transition the application "{0}" to running mode due to error {1}

Category:
Deployer

Cause:
The cause of this error is likely in the application or the application subsystem for that application type.

Action:
Review the exception and attempt to repair the application level. Then reinitiate the deployment request.

BEA-149248
Failed to transition the application "{0}" to administration mode due to error {1}.

Category:
Deployer

Cause:
The cause of this error is likely in the application or the application subsystem for that application type.

Action:
Review the exception and attempt to repair the application level. Then reinitiate the deployment request.

BEA-149250
Unable to unprepare the application "{0}".

Category:
Deployer

Cause:
This was an unexpected error.

Action:
Report this error to My Oracle Support.

BEA-149251
Operation {0} failed for application "{1}". Error: {2}

Category:
Deployer

Cause:
See the exception in the message body.

Action:
Typically, no action is required.

BEA-149252
No deployment "{1}" found for operation {0}.

Category:
Deployer

Cause:
See the message body.

Action:
No action is required.

BEA-149256
Failed to find deployment for application "{0}".

Category:
Deployer

Cause:
The cause of this error is likely that the deployment was not properly created, possibly because it may not have proper descriptors.

Action:
Review the exception and attempt to repair the application level. Then reinitiate the deployment request.

BEA-149257
Rejecting the attempt to distribute application or shared library "{0}" while the application is running (in state {1}). This operation is not permitted while the application is running or has pending updates.

Category:
Deployer

Cause:
The application or shared library was not stopped or had pending updates.

Action:
Verify that the application or shared library is stopped or has no pending updates before attempting to distribute it. You may also consider redeploying the application.

BEA-149258
The server failed to completely remove the staged files "{1}" for application "{0}". Check the directory and ensure that no other application is using this directory. This will result in inappropriate results when this server is partitioned and tries to deploy this application.

Category:
Deployer

Cause:
Another application might be using the files under a staging directory.

Action:
Delete the appropriate staged files manually.

BEA-149259
Server "{0}" in cluster "{1}" is being brought up in administration state due to failed deployments.

Category:
Deployer

Cause:
This problem occurred due to failed deployments, which are already logged.

Action:
Correct the cause of the deployment errors, redeploy the failed deployments, and resume or restart the server in the cluster.

BEA-149260
A failure occurred during application startup.

Category:
Deployer

Cause:
Check the error stack trace for details of the failure.

Action:
Correct the cause of the application failure, if possible, and redeploy the application or restart the server. If it is an Oracle internal application, report it to My Oracle Support.

BEA-149264
Invalid redeploy attempt on application "{0}". There was an attempt to redeploy the application when the application was not running.

Category:
Deployer

Cause:
The application was stopped.

Action:
Start the application.

BEA-149265
Failure occurred in the execution of deployment request with ID "{0}" for task "{1}" on [partition-name: {2}]. Error is: "{3}"

Category:
Deployer

Cause:
See the reported error in the message body.

Action:
Start the application.

BEA-149266
Illegal state for operation deploy: "{0}".

Category:
Deployer

Cause:
The deploy operation was called on an application that was not new.

Action:
Verify that the specified application name and operation are correct.

BEA-149267
Cancel operation on deployment task "{0}" on server "{1}" failed.

Category:
Deployer

Cause:
See the underlying exception.

Action:
Take action based on the underlying exception.

BEA-149268
Static deployment of non-versioned application "{0}" failed due to a version being defined in its manifest file.

Category:
Deployer

Cause:
The manifest file was modified with a version for a non-versioned application.

Action:
Remove the application and redeploy it with a version.

BEA-149269
Static file redeployment and module level redeployment cannot be in the same deployment task. Check the usage.

Category:
Deployer

Cause:
The server cannot determine which type of redeployment should be processed.

Action:
Correct the deployment option.

BEA-149319
{0}: List of servers being worked upon are {1}.

Category:
Management

Cause:
{0}

Action:
None

BEA-149400
Activating application: {0}

Category:
Application Poller

Cause:
This is an informational message.

Action:
No action is required.

BEA-149401
Removing application: {0}

Category:
Application Poller

Cause:
This is an informational message.

Action:
No action is required.

BEA-149403
Application {0} deployed from the applications directory has components that are deployed on servers other than the Administration Server. Refresh of static content (such as JSPs and HTML pages) will not be automatically propagated to the Managed Servers. To propagate your changes to the Managed Servers, you must redeploy the application by touching the REDEPLOY file.

Category:
Application Poller

Cause:
This is a warning message only.

Action:
Touch the REDEPLOY file to properly redeploy the application. The REDEPLOY file is located in the same directory as the deployment descriptor. For EAR files, it is located in META-INF/REDEPLOY.

BEA-149407
An error occurred while undeploying application {0} : {1}.

Category:
Application Poller

Cause:
Undeployment can fail for many reasons.

Action:
Review the error message and take corrective action.

BEA-149408
An exception occurred while deploying an application {0}: {1}.

Category:
Application Poller

Cause:
Deployment of an application can fail for many reasons. Refer to the exception details.

Action:
Review the exception. To redeploy the application after correcting the error condition, touch the file called REDEPLOY in the META-INF or WEB-INF directory of the exploded application.

BEA-149409
Caught exception while starting the applications poller on server start {0}.

Category:
Application Poller

Cause:
A misconfigured application may be present in the applications directory.

Action:
Review the exception message in the server log.

BEA-149410
Runtime deployment error while deploying - {0}.

Category:
Application Poller

Cause:
The cause of this error is unknown.

Action:
Refer to the runtime error in the message.

BEA-149411
I/O exception was encountered {0}.

Category:
Application Poller

Cause:
An I/O exception can occur during file read/write while deploying an application.

Action:
Take corrective action based on the exception message details.

BEA-149412
Application "{0}" is being redeployed, because it changed since the previous server run.

Category:
Application Poller

Cause:
This application is deployed using auto-deployment. The application was modified while the server was down, hence it will be redeployed by the auto-deployment poller. Another possible cause is that the internal file used by the poller was removed or moved from disk. In that case, it assumes applications have changed.

Action:
No action is required. This is an informational message to explain why this deployment was redeployed after its deployment at startup.

BEA-149414
Could not create directory for autodeployed applications: {0}

Category:
Application Poller

Cause:
This may be an error on the local file system of the Administration Server.

Action:
Correct the error by creating the directory or making sure read/write permissions exist.

BEA-149415
An exception was encountered while migrating application poller applications {0}.

Category:
Application Poller

Cause:
An exception occurred while modifying application's path.

Action:
Report this error to My Oracle Support.

BEA-149416
Application migrated {0} - {1}

Category:
Application Poller

Cause:
This is informational message.

Action:
No action is required.

BEA-149417
Another process is using the file "{0}". The server will attempt to deploy the application once it is unlocked by the other process.

Category:
Application Poller

Cause:
Another process has a lock on the file that is in the hot deploy directory. The application could still be in the process of being copied.

Action:
Ensure that no other process is attempting to lock part or all of this application file. If the copy is ongoing, then no action should be necessary.

BEA-149500
An exception occurred while registering the MBean {0}.

Category:
JMX

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
This is an internal WebLogic Server error and should be reported as a bug to My Oracle Support.

BEA-149501
An exception occurred while registering the MBean {0} at property {1}.

Category:
JMX

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
This is an internal WebLogic Server error and should be reported as a bug to My Oracle Support.

BEA-149502
An exception occurred while unregistering the MBean {0}.

Category:
JMX

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
This is an internal WebLogic Server error and should be reported as a bug to My Oracle Support.

BEA-149503
An exception occurred while unregistering the MBean {0} at property {1}.

Category:
JMX

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
This is an internal WebLogic Server error and should be reported as a bug to My Oracle Support.

BEA-149504
The Administration Server was unable to establish JMX Connectivity with the {0} at the JMX Service URL of {1}.

Category:
JMX

Cause:
This is likely due to a misconfiguration of the Managed Server. Often this is associated with the use of the administration channel.

Action:
Ensure that the Managed Server adminstration ports are properly configured. It may be helpful to review the documentation on the administration channel configuration.

BEA-149505
The Administration Server was unable to establish JMX Connectivity with the {0} at the JMX Service URL of {1}.

Category:
JMX

Cause:
This is likely because the Managed Server is simply not running. It may indicated that the administration channels are not properly configured.

Action:
Ensure that the Managed Server administration ports are properly configured. It may be helpful to review the documentation on the administration channel configuration.

BEA-149506
Established JMX Connectivity with {0} at the JMX Service URL of {1}.

Category:
JMX

Cause:
This is a normal operation.

Action:
No action is required.

BEA-149507
JMX Connectivity has been discontinued with the Managed Server {0}.

Category:
JMX

Cause:
This message is logged whenever a Managed Server is shut down.

Action:
No action is required.

BEA-149508
Unable to establish JMX Connectivity with the Administration Server.

Category:
JMX

Cause:
This may have occurred because the Administration Server is not currently available or it may indicate a misconfiguration of the administrative channels.

Action:
If the Administration Server is currently running, the administrator should consult the documentation on the administration channel configuration.

BEA-149509
Unable to establish JMX connectivity with the Administration Server {0} at {1}.

Category:
JMX

Cause:
This may have occurred because the Administration Server is not currently available or it may indicate a misconfiguration of the administrative channels.

Action:
If the Administration Server is currently running, the administrator should consult the documentation on the administration channel configuration.

BEA-149510
Unable to establish JMX Connectivity with the Administration Server {0} at {1}.

Category:
JMX

Cause:
This may have occurred because the Administration Server is not currently available or it may indicate a misconfiguration of the administrative channels.

Action:
If the Administration Server is currently running, the administrator should consult the documentation on the administration channel configuration.

BEA-149511
Established JMX Connectivity with the Administration Server {0} at {1}.

Category:
JMX

Cause:
This is a normal operation.

Action:
No action is required.

BEA-149512
JMX Connector Server started at {0}.

Category:
JMX

Cause:
This is a normal operation.

Action:
No action is required.

BEA-149513
JMX Connector Server stopped at {0}.

Category:
JMX

Cause:
This is a normal operation.

Action:
No action is required.

BEA-149515
An error was encountered getting the attribute {1} on the MBean {0} during a call to getAttributes.

Category:
JMX

Cause:
This problem is the result of an internal WebLogic Server error in the WebLogic Server JMX implementation.

Action:
Report this message to My Oracle Support.

BEA-149516
An error was encountered when setting the attribute {1} on the MBean {0} during a call to setAttributes.

Category:
JMX

Cause:
This problem is the result of an internal WebLogic Server error in the WebLogic Server JMX implementation.

Action:
Report this message to My Oracle Support.

BEA-149518
An attempt was made to unregister the {0} WebLogic Server MBean through JMX.

Category:
JMX

Cause:
Avoid using the JMX API to unregister a WebLogic Server MBean.

Action:
Use the WebLogic Server APIs to control the configuration of the server environment.

BEA-149519
The JMX Service URL {1} for Managed Server {0} was malformed.

Category:
JMX

Cause:
The URL used to contact a Managed Server was malformed.

Action:
See the exception included with this message to determine the proper action.

BEA-149520
An attempt was made to register an MBean with ObjectName {0} ObjectName in com.bea domain.

Category:
JMX

Cause:
An attempt was made to register an MBean with the com.bea domain name.

Action:
Register your MBeans with another domain name.

BEA-149521
An exception occurred during the processing of JMX Connectivity with the Administration Server: {0}

Category:
JMX

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Refer to the embedded exception information for more details and troubleshoot based on that information.

BEA-149522
No credentials were provided.

Category:
JMX

Cause:
Credentials are required when connecting through Remote MAnagement Interface (RMI).

Action:
Retry the connection, supplying a username and password.

BEA-149523
RmiServerManager not found.

Category:
JMX

Cause:
This problem is the result of an internal WebLogic Server error in the WebLogic Server JMX implementation.

Action:
Report this message to My Oracle Support.

BEA-149524
JMX Connector Server started at "{0}".

Category:
JMX

Cause:
This is a normal operation.

Action:
No action is required.

BEA-149525
JMX Connector Server stopped at "{0}".

Category:
JMX

Cause:
This is a normal operation.

Action:
No action is required.

BEA-149526
Cannot access the attribute "{0}"{ from a partition "{{1}"{ on MBean "{{2}"{ because it is annotated with @ExcludeFromPartition or its interface is annotated with @ExcludeFromPartition.

Category:
JMX

Cause:
An MBean or its attribute is annotated with @ExcludeFromPartition.

Action:
Either do not access the attribute, or remove the @ExcludeFromPartition annotation from the MBean interface or attribute.

BEA-149527
Cannot access the operation "{{0}"{ from a partition "{{1}" on MBean "{2}" because it is annotated with @ExcludeFromPartition or the MBean interface is annotated with @ExcludeFromPartition.

Category:
JMX

Cause:
An attempt was made to access an operation annotated with @ExcludeFromPartition.

Action:
Either do not access the operation, or remove the @ExcludeFromPartition annotation from the operation or MBean interface.

BEA-149528
Cannot get the attribute "{0}" on MBean "{2}" from the partition "{1}". Either the attribute does not exist or the attribute is not visible to the partition.

Category:
JMX

Cause:
The attribute does not exist or the attribute is not visible to the partition.

Action:
If the attribute does not exist in the MBean, either change the MBean interface and its implementation to add the attribute or change to get other existing attributes. If the attribute exists but is not visible to the partition, annotate the attribute with @VisibleToPartitions ALWAYS.

BEA-149529
Cannot set the attribute "{0}" on MBean "{2}" from the partition "{1}". Either the MBean does not contain the attribute or the MBean attribute is not visible to the partition.

Category:
JMX

Cause:
The attribute does not exist or the attribute is not visible to the partition.

Action:
If the attribute does not exist in the MBean, either change the MBean interface and its implementation to add the attribute or change to set other existing attributes. If the attribute exists but is not visible to the partition, annotate the attribute with @VisibleToPartitions ALWAYS.

BEA-149530
Cannot invoke the operation "{0}" on MBean "{2}" from partition "{1}". Either the MBean does not contain the operation or the operation is not visible to the partition.

Category:
JMX

Cause:
The MBean does not contain the operation or the operation is not visible to the partition.

Action:
If the operation does not exist in the MBean, either change the MBean interface and its implementation to add the operation or invoke other existing operations. If the operation exists but is not visible to the partition, annotate the operation with @VisibleToPartitions ALWAYS.

BEA-149531
Cannot find the MBean "{0}" in partition "{1}".

Category:
JMX

Cause:
The MBean is not visible to partitions.

Action:
The MBean is not registered correctly or the MBean needs to be annotated with @VisibleToPartitions ALWAYS.

BEA-149532
The MBean "{0}" contains a different Partition key property value in the ObjectName: found "{1}", should be "{2}".

Category:
JMX

Cause:
The MBean ObjectName is not correct.

Action:
Provide an MBean ObjectName that is owned by the current partition.

BEA-149533
Cannot invoke the operation "{0}" on MBean "{2}" from partition "{1}" because one or more of the MBean operation parameters is not visible to partitions: {3}

Category:
JMX

Cause:
The MBean passed in as an operation parameter is not visible to partitions.

Action:
Annotate the MBean passed in as an operation paramter with @VisibleToPartitions ALWAYS.

BEA-149534
An exception occurred while calling queryNames for all mBeans from Managed Server: {0}.

Category:
JMX

Cause:
The size of the result of call queryNames for all mBeans exceeds the configured Maximum Message Size for the Administration Server.

Action:
Increase the Maximum Message Size configured for the Administration Server, or disable the indicated Managed Server notifications by using the property weblogic.management.disableManagedServerNotifications=true.

BEA-149535
JMX Resiliency Activity Server={0} : {1}

Category:
JMX

Cause:
Refer to the embedded info fore more details.

Action:
Refer to the embedded info for more details.

BEA-149536
Received a connect event for a server : {0} to establish JMX Connectivity, which does not exist in the domain configuration. It will be ignored.

Category:
JMX

Cause:
A managed server is RUNNING while it has been deleted from domain configuration in offline mode on admin server machine.

Action:
Validate the domain configuration, and shutdown the managed server.

BEA-149601
The deployment framework was unable to resume accepting requests.

Category:
Deployer

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-149603
The deployment framework was unable to cleanly shut down.

Category:
Deployer

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-149605
Failed to create App/Comp MBeans for AppDeploymentMBean {0}. Error - {1}.

Category:
Deployer

Cause:
An error was found in the AppDeploymentMBean.

Action:
Reconfigure the AppDeploymentMBean.

BEA-149606
Failed to configure deployment MBean for {0}.

Category:
Deployer

Cause:
An error was found while configuring a deployment MBean.

Action:
Review the application and reconfigure it.

BEA-149607
Failed to persist state for deployment with name {0}. {1}

Category:
Deployer

Cause:
See the exception for more details on the cause of this problem.

Action:
See the exception. Undeploy and deploy after correcting the problem.

BEA-149608
Unknown type of deployable: "{0}"

Category:
Deployer

Cause:
The type of deployable: "{0}" is unknown.

Action:
See the exception and check for preceding messages in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149609
AppRuntimeStateRuntime only available on the Administration Server.

Category:
Deployer

Cause:
AppRuntimeStateRuntime only available on the Administration Server.

Action:
Ensure that the Administration Server is running and check for preceding messages in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149610
Problems were encountered while creating the persistent store.

Category:
Deployer

Cause:
An exception occurred: {0}

Action:
See the exception and check for preceding messages in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149611
Problems were encountered while creating the persistent store.

Category:
Deployer

Cause:
An exception occurred: {0}

Action:
See the exception and check for preceding messages in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149612
Problems were encountered while saving to the persistent store for "{0}".

Category:
Deployer

Cause:
{1}

Action:
See the exception and check for preceding messages in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149613
Problems were encountered while deleting from the persistent store for "{0}".

Category:
Deployer

Cause:
{1}

Action:
Check for preceding messages in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149614
There were problems during the server disconnect for listener "{0}". {1}

Category:
Deployer

Cause:
{1}

Action:
Check for preceding messages in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149615
Unrecognized type: "{0}".

Category:
Deployer

Cause:
There was an unrecognized type: "{0}".

Action:
Check for preceding messages in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149616
A critical internal application {0} was not deployed. Error: {1}

Category:
Deployer

Cause:
The cause of this error is unknown.

Action:
Check for preceding conflict start message in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-149617
Non-critical internal application {0} was not deployed. Error: {1}

Category:
Deployer

Cause:
An internal application may not have been installed.

Action:
Install the WebLogic Server internal application by running the WebLogic Server installer and choosing the relevant option.

BEA-149618
Unable to deploy an internal management Web application - {0}. Managed Servers may be unable to start.

Category:
Deployer

Cause:
WebLogic Server was unable to find the relevant WAR files in RootDirectory/lib. This might also be an internal failure. See the exception stack trace for more details.

Action:
If you are not running the server from the directory where WebLogic Server was installed, ensure that the value of the provided RootDirectory matches the directory where the WebLogic Server product was installed. Verify that a file with the application name in the log message (with a .war extension) is present in RootDirectory/lib. If not, contact My Oracle Support.

BEA-149619
The deletion of configuration file {0} failed.

Category:
Deployer

Cause:
An error occurred while deleting the file.

Action:
Ensure that no processes have the file open for write. Ensure that the permissions on the directory allow for delete of this file.

BEA-149621
An error occurred while the Administration Server was performing configuration recovery. Error is : "{0}".

Category:
Deployer

Cause:
See the exception details for the cause.

Action:
Stop the server and do configuration recovery manually.

BEA-149622
Could not get file lock used to serialize access to configuration files due to {0}.

Category:
Deployer

Cause:
The lock could not be obtained before the specified timeout period has elapsed.

Action:
Verify the configuration files and ensure no server has hung, thereby not releasing the lock.

BEA-149623
Unable to create DeploymentManagerMBean.

Category:
Deployer

Cause:
This may occur if an error at the JMX level exists.

Action:
Report this problem to Oracle Customer Support.

BEA-150000
An error occurred while establishing a connection back to the Adminstration Server {0} during startup. Since bootstrap succeeded, check that {0} uniquely identifies the Administration Server.

Category:
Configuration Management

Cause:
An improper Administration Server URL has been specified, or the Administration Server is not available at the specified URL. Commonly this is because the Managed Server shares an adminstration URL with the Administration Server. Another possibility is that the host identified by {0}, or the local host, is not configured properly. For instance, an /etc/hosts or DNS lookup on the hostname results in a loopback address.

Action:
Verify that the URL specified for the Administration Server is valid, unique and that the Administration Server is available and listening at the specified URL. A common problem is that the administration port is enabled and both the Administration Server and Managed Server are running on the same machine. In this instance a different administration port should be selected for the Managed Server. Another possibility is that the host identified by {0}, or the local host, is not configured properly. For instance, an /etc/hosts or DNS lookup on the hostname results in a loopback address.

BEA-150001
An error occurred while connecting to the Administration Server to bootstrap through the URL: {0}, user: {1}.

Category:
Configuration Management

Cause:
The Administration Server might currently be unavailable or the specified URL: {0} or username: {1} might be invalid.

Action:
Confirm that the designated Administration Server is running and that the specified URL: {0} and username: {1} are valid for this configuration.

BEA-150014
The Managed Server Independence feature is disabled for this server ({0}).

Category:
Configuration Management

Cause:
The specified Administration Server is either incorrect or not reachable on the network.

Action:
Ensure that the Administration Server is running and reachable by this server, or set the ManagedServerIndependenceEnabled attribute on this server to true.

BEA-150018
This server is being started in Managed Server independence mode in the absence of the Administration Server.

Category:
Configuration Management

Cause:
The Managed Server was unable to communicate with the Adminstration Server at the provided URL because the specified Administration Server either was not running or was partitioned.

Action:
Restart the Administration Server with Managed Server discovery enabled so that the running Managed Server can synchronize its configuration with the Administration Server and become centrally managed.

BEA-150020
The Managed Server could not reach the Administration Server at {0}.

Category:
Configuration Management

Cause:
The Managed Server was given a URL on which the Administration Server could not be contacted.

Action:
Inspect the Administration Server address:port provided to the Managed Server that is being started. This address should be changed to point to the Administration Server rather than resolving locally on the Managed Server.

BEA-150021
The Administration Server failed to authenticate the identity of the user {0} starting the Managed Server. The reason for the error is {1}.

Category:
Configuration Management

Cause:
The username and password combination was not correct.

Action:
Inspect the username and password of the user starting the Managed Server and supply the correct credentials. The username and password are specified on startup with -Dweblogic.management.username and -Dweblogic.management.password command line options to the java weblogic.Server command.

BEA-150024
The server name {0} is being started again as a Managed Server.

Category:
Configuration Management

Cause:
The Administration Server is being started as the Managed Server.

Action:
Specify a different server name to start.

BEA-150026
The server {0} being started is at an invalid release level {1} with respect to the Administration Server {2}. The major version of the Administration Server must be less than or equal to the major version of the Managed Server.

Category:
Configuration Management

Cause:
A Managed Server of a different major release is attempting to start from the Administration Server.

Action:
Point the Managed Server to an Administration Server at the correct release level.

BEA-150027
Server name {0} not found in domain {1}.

Category:
Configuration Management

Cause:
A Managed Server is started with -Dweblogic.Name with a value that was not configured in the domain.

Action:
Specify the correct value of the parameter -Dweblogic.Name.

BEA-150028
A security failure or an exception occurred when retrieving the bootstrap information for the Managed Server.

Category:
Configuration Management

Cause:
An invalid username and password might have been supplied while starting the Managed Server.

Action:
Supply the correct credentials. Take corrective action based on the exception details.

BEA-150032
The Managed Server did not provide any version details at initial contact.

Category:
Configuration Management

Cause:
A Managed Server of a different major and minor release is attempting to start from the Administration Server.

Action:
Point the Managed Server to an Administration Server at the correct release level.

BEA-150034
An attempt was made to download the configuration for the server {0} without the required credentials.

Category:
Configuration Management

Cause:
This should not happen during normal operations and may represent an attempt to compromise the server.

Action:
Identify the server from which the connection was made and ensure that the username and password are being properly specified.

BEA-150035
An attempt was made to download the configuration for the server {0} by the user {1} with an invalid password.

Category:
Configuration Management

Cause:
This should not happen during normal operations and may represent an attempt to compromise the server.

Action:
Identify the server from which the connection was made and ensure that the username and password are being properly specified.

BEA-150036
An attempt was made to download the configuration for the server {0} by the unauthorized user {1}.

Category:
Configuration Management

Cause:
This should not happen during normal operations and may represent an attempt to compromise the server.

Action:
Identify the server from which the connection was made and ensure that the username and password are being properly specified.

BEA-150038
A configuration file was found in the parent directory {0}, but the root directory is empty.

Category:
Configuration Management

Cause:
This message indicates that a configuration file exists in the parent of the root directory.

Action:
If the specified root directory is not correct, then take appropriate action. Otherwise, this message may be ignored.

BEA-150039
The server name could not be determined.

Category:
Configuration Management

Cause:
The name was not specified or the specified name does not exist in the config.xml file.

Action:
Specify the correct value of the parameter -Dweblogic.Name.

BEA-150041
The server name {0} is unknown to the Administration Server. Check if restart is required.

Category:
Configuration Management

Cause:
The -Dweblogic.Name command line property specifies a server that does not exist in the configuration that is active on the Administration Server. This can occur if the Managed Server

was added to the configuration along with non-dynamic changes that affect the Administration Server. In this case, the Administration Server must be restarted.

Action:
Check to see if the Administration Server is marked as needing a restart. If it is, then restart the Administration Server before trying to start this Managed Server. Check the configuration for the list of configured servers.

BEA-150042
The -Dweblogic.management.server value of {0} does not specify a port that has administrator privileges. Change the startup command to specify a -Dweblogic.management.server value of {1}. This server will remain in Managed Server independence mode until it is started with a port that has administrator privileges.

Category:
Configuration Management

Cause:
The specified Administration Server port does not support the administrator traffic required to allow the Managed Server to communicate with the Administration server.

Action:
Change the -Dweblogic.management.server property to specify a port that has administator privileges.

BEA-150043
Cannot delete server {0} in domain {1} while the server is running. Please shut down the server in order to delete the server.

Category:
Configuration Management

Cause:
An attempt was made to delete a static or dynamic Managed Server while it was still running.

Action:
Shut down the server and retry the change that deleted the server.

BEA-150044
The protection domain of class {1} does not have permission to inject a service from descriptor {0}. The protection domain is {2} and the permission is {3}.

Category:
Configuration Management

Cause:
A service does not have permission to inject a service that was found for it. The creation of the service will fail if no other appropriate service can be found to satisfy the injection point.

Action:
Ensure that the protection domain of the class has rights to the specified permission.

BEA-150045
Edit session name {0} contains illegal character(s) and cannot be used. Choose a different name.

Category:
Configuration Management

Cause:
The specified edit session name does not meet the criteria for this component. It contains illegal character(s).

Action:
Choose a different name.

BEA-150046
An edit session named {0} already exists. Choose a different name.

Category:
Configuration Management

Cause:
You attempted to create two edit sessions with the same name.

Action:
Choose a different name.

BEA-150048
Cannot destroy default edit session.

Category:
Configuration Management

Cause:
You attempted to destroy the default edit session.

Action:
Use a named edit session.

BEA-150049
The JMS server named {0} has a temporary template configured. The JMSSystemResourceMBean name of the module containing the temporary template is {1}, and the template name is {2}. However, a JMSSystemResourceMBean of name {1} could not be found. The JMS server {0} will not boot until this problem has been fixed.

Category:
Configuration Management

Cause:
The temporary template for a JMS server must come from a JMSSystemResourceMBean. A common mistake is to put the temporary template into an AppDeployment. However, because the temporary template must be owned by the administrator, all temporary templates must come from JMSSystemResourceMBeans, not AppDeployments.

Action:
Put the temporary template into a JMSSystemResource.

BEA-150050
Cannot destroy DOMAIN partition.

Category:
Configuration Management

Cause:
You attempted to destroy DOMAIN partition. This is not a valid operation.

Action:
Use a named edit session.

BEA-150051
Cannot remove edit session. This edit session belongs to a different partition.

Category:
Configuration Management

Cause:
Entities from other partitions cannot be operated on in an edit session for a given partition.

Action:
Review the management request.

BEA-150052
Edit session {0} is locked by user {1} and cannot be deleted. Administrator permissions required.

Category:
Configuration Management

Cause:
The edit session is currently being edited.

Action:
Review the management request or use force=true while logged in as an administrator.

BEA-150053
Edit session {0} is locked by user {1} and cannot be deleted. Use destroyEditSession("{0}", force = true) to override.

Category:
Configuration Management

Cause:
The edit session is currently being edited.

Action:
Review management request or use force=true.

BEA-150054
Edit session {0} contains changes pending activation. Destroy edit session command has been aborted. Use destroyEditSession("{0}", force = true) to force the destroy operation.

Category:
Configuration Management

Cause:
The edit session contains changes that are pending activation.

Action:
Review the management request or use force=true.

BEA-150055
Edit session {0} was created by user {1}. Administrator permissions required.

Category:
Configuration Management

Cause:
The caller is not the creator of the edit session.

Action:
Review the management request or use force=true while logged in as an administrator.

BEA-150056
Edit session {0} was created by user {1}. Destroy edit session command has been aborted. Use destroyEditSession("{0}", force = true) to force the destroy operation.

Category:
Configuration Management

Cause:
The caller is not the creator of the edit session.

Action:
Review the management request or use force=true.

BEA-150057
A failure has occurred during service lookup, bind or unbind from descriptor {0} using permission {1} with: {2}

Category:
Configuration Management

Cause:
The operation being performed does not have permission to lookup, bind or unbind the service descriptor.

Action:
Carefully read the returned error to determine what action is required.

BEA-150058
The Restart In Place setting of Persistent Store "{0}" is configured to True and will be ignored. This setting is ignored when a store is directly targeted to a server within a cluster or is targeted to a migratable target. If a store is targeted to a migratable target, you can tune restart in place on the migratable target itself instead of on the store.

Category:
Configuration Management

Cause:
RestartInPlace is not supported when the store is targeted to a Single Server within a Cluster.

Action:
No action is required.

BEA-150059
RestartInPlace of ReplicatedStore {0} is configured to True, which is invalid and will be ignored, when the store is targeted to a Single Server or its Migration Policy is Off

Category:
Configuration Management

Cause:
ReplicatedStore doesn't support RestartInPlace when the store is targeted to a Single Server or its Migration Policy is Off.

Action:
No action is required.

BEA-159900
USER {0} CREATED {1}

Category:
Configuration Audit

Cause:
See the message body.

Action:
No action is required.

BEA-159901
USER {0} CREATE {1} FAILED {2}

Category:
Configuration Audit

Cause:
See the message body.

Action:
No action is required.

BEA-159902
USER {0} REMOVED {1}

Category:
Configuration Audit

Cause:
See the message body.

Action:
No action is required.

BEA-159903
USER {0} REMOVE {1} FAILED {2}

Category:
Configuration Audit

Cause:
See the message body.

Action:
No action is required.

BEA-159904
USER {0} MODIFIED {1} ATTRIBUTE {2} FROM {3} TO {4}

Category:
Configuration Audit

Cause:
See the message body.

Action:
No action is required.

BEA-159905
USER {0} MODIFY {1} ATTRIBUTE {2} FROM {3} TO {4} FAILED {5}

Category:
Configuration Audit

Cause:
See the message body.

Action:
No action is required.

BEA-159907
USER {0} INVOKED ON {1} METHOD {2} PARAMS {3}

Category:
Configuration Audit

Cause:
See the message body.

Action:
No action is required.

BEA-159908
USER {0} INVOKED ON {1} METHOD {2} PARAMS {3} FAILED {4}

Category:
Configuration Audit

Cause:
See the message body.

Action:
No action is required.

BEA-159909
USER {0}, configuration auditing is enabled.

Category:
Configuration Audit

Cause:
See the message body.

Action:
No action is required.

BEA-159910
USER {0}, configuration auditing is disabled.

Category:
Configuration Audit

Cause:
See the message body.

Action:
No action is required.

BEA-159911
Invalid number {0} was found while encrypting clear text passwords.

Category:
Configuration Audit

Cause:
See the message body.

Action:
No action is required.

BEA-160001
Error deploying {0}: {1}

Category:
J2EE

Cause:
The application is misconfigured. See the logged exception for more details.

Action:
Check the config.xml to ensure that the component MBean is wrapped in a valid application MBean and that it has a valid URI and target attribute. Check the server log for errors.

BEA-160032
Unable to create mbean Name: {0} Type: {1} Exception: {2}

Category:
J2EE

Cause:
See message body.

Action:
See exception message logged.

BEA-160039
Failed to undeploy a mail session.

Category:
J2EE

Cause:
There was a JNDI unbind error.

Action:
Check the error that is reported in the exception.

BEA-160040
Deployed MailSession named {0}

Category:
J2EE

Cause:
This is an information message.

Action:
No action is required.

BEA-160041
Undeployed MailSession named {0}.

Category:
J2EE

Cause:
This is an information message.

Action:
No action is required.

BEA-160069
Error while looking for Web services files: {0}

Category:
J2EE

Cause:
An IOException occurred while accessing Web services files.

Action:
See the stack trace for details.

BEA-160083
Error: The ejb-link "{0}" declared in the ejb-ref or ejb-local-ref "{1}" for EJB "{2}" in the module "{3}" could not be resolved. The ejb-jar file "{4}" could not be found in this EAR file.

Category:
J2EE

Cause:
The path to the target EJB does not exist in the application.

Action:
The ejb-link must be fixed to point to the module containing the target EJB.

BEA-160084
Error: The ejb-link "{0}" declared in the ejb-ref or ejb-local-ref "{1}" in the module "{2}" could not be resolved. The ejb-jar file "{3}" could not be found in this ear file.

Category:
J2EE

Cause:
The path to the target EJB does not exist in the application.

Action:
The ejb-link must be fixed to point to the module containing the target EJB.

BEA-160085
Error: The ejb-link "{0}" declared in the ejb-ref or ejb-local-ref "{1}" for EJB "{2}" in the module "{3}" could not be resolved. The EAR module "{4}" does not contain an EJB with the name "{5}".

Category:
J2EE

Cause:
The specified EJB does not exist in the module.

Action:
The ejb-link must be fixed to point to a valid EJB.

BEA-160086
Error: The ejb-link "{0}" declared in the ejb-ref or ejb-local-ref "{1}" in the module "{2}" could not be resolved. The EAR module "{3}" does not contain an EJB with the name "{4}".

Category:
J2EE

Cause:
The specified EJB does not exist in the module.

Action:
The ejb-link must be fixed to point to a valid EJB.

BEA-160087
Error: The ejb-link "{0}" declared in the ejb-ref or ejb-local-ref "{1}" for EJB "{2}" in the module "{3}" did not resolve to a bean with component interfaces. Ensure that the link is correct.

Category:
J2EE

Cause:
The link did not resolve to a valid EJB.

Action:
The ejb-link must be fixed to point to a valid EJB.

BEA-160088
Error: The ejb-link "{0}" declared in the ejb-ref or ejb-local-ref "{1}" in the module "{2}" did not resolve to a bean with component interfaces. Ensure that the link is correct.

Category:
J2EE

Cause:
The link did not resolve to a valid EJB.

Action:
The ejb-link must be fixed to point to a valid EJB.

BEA-160089
Error: The ejb-link "{0}" declared in the ejb-ref or ejb-local-ref "{1}" for EJB "{2}" in the module "{3}" could not be resolved. No EJB named "{0}" with component interfaces exists in the application. Ensure that the link is correct.

Category:
J2EE

Cause:
The specified EJB does not exist in the module.

Action:
The ejb-link must be fixed to point to a valid EJB.

BEA-160090
Error: The ejb-link "{0}" declared in the ejb-ref or ejb-local-ref "{1}" in the module "{2}" could not be resolved. No EJB named "{0}" with component interfaces exists in the application. Ensure that the link is correct.

Category:
J2EE

Cause:
The specified EJB does not exist in the module.

Action:
The ejb-link must be fixed to point to a valid EJB.

BEA-160091
Error: The ejb-link "{0}" declared in the ejb-ref or ejb-local-ref "{1}" for EJB "{2}" in the module "{3}" is ambiguous. The following list of application modules contain an EJB with the name "{0}": {4}. Qualify this ejb-link to remove the ambiguity.

Category:
J2EE

Cause:
The ejb-link is unqualified and resolves to multiple EJBs in the application.

Action:
The ejb-link must be fixed to point to a single EJB.

BEA-160092
Error: The ejb-link "{0}" declared in the ejb-ref or ejb-local-ref "{1}" in the module "{2}" is ambiguous. The following list of application modules contain an EJB with the name "{0}": {3}. Qualify this ejb-link to remove the ambiguity.

Category:
J2EE

Cause:
The ejb-link is unqualified and resolves to multiple EJBs in the application.

Action:
The ejb-link must be fixed to point to a single EJB.

BEA-160093
Error: The ejb-link "{0}" declared in the {1} "{2}" for EJB "{3}" in the module "{4}" could not be established. The target of the ejb-link does not have {5} interfaces. Ensure that the link is correct.

Category:
J2EE

Cause:
The ejb-link resolves to an EJB which does not expose interfaces compatible with the ref type.

Action:
Ensure that the target of the ejb-link is correct. If it is, either add component interfaces to this EJB that are compatible with the ref type or change the ref type to be compatible with the interfaces exposed by the target EJB.

BEA-160094
Error: The ejb-link "{0}" declared in the {1} "{2}" in the module "{3}" could not be established. The target of the ejb-link does not have {4} interfaces. Ensure that the link is correct.

Category:
J2EE

Cause:
The ejb-link resolves to an EJB which does not expose interfaces compatible with the ref type.

Action:
Ensure that the target of the ejb-link is correct. If it is, either add component interfaces to this EJB that are compatible with the ref type or change the ref type to be compatible with the interfaces exposed by the target EJB.

BEA-160095
Warning: The {0} "{1}" for EJB "{2}" in the module "{3}" has an invalid {4} element value "{5}". The target bean does not declare that {4} interface. Ensure that the values are correct.

Category:
J2EE

Cause:
The home or component interface name in the ejb-ref or ejb-local-ref does not match the home or component interface name of the target EJB.

Action:
Ensure that the target of the ejb-link is correct. If it is, fix the ejb-ref or ejb-local-ref so that the names of the home and component interfaces match the names of the home and component interfaces of the target EJB.

BEA-160096
Warning: The {0} "{1}" in the module "{2}" has an invalid {3} element value "{4}". The target bean does not declare that {3} interface. Ensure that the values are correct.

Category:
J2EE

Cause:
The home or component interface name in the ejb-ref or ejb-local-ref does not match the home, component or business interface name of the target EJB.

Action:
Ensure that the target of the ejb-link is correct. If it is, fix the ejb-ref or ejb-local-ref so that the names of the home and component interfaces match the names of the home and component interfaces of the target EJB.

BEA-160098
Unable to parse the file "{0}" because it uses an invalid encoding name, "{1}". All deployment descriptors must use an IANA or Java encoding name. Change the encoding of the descriptor to be a supported encoding.

Category:
J2EE

Cause:
The encoding name used by the deployment descriptor is not supported.

Action:
Change the encoding name of the deployment descriptor to an IANA or Java encoding name.

BEA-160100
Could not deploy role: {0} for application: {1}.

Category:
J2EE

Cause:
The application could not deploy the role defined in application.xml.

Action:
Ensure that the security is configured properly in the server. Also, check the stack trace for the exact cause.

BEA-160101
Error: The ejb-link "{0}" declared in the ejb-ref or ejb-local-ref "{1}" in the application module "{2}" could not be resolved. The target EJB for the ejb-ref could not be found. Ensure that the link is correct.

Category:
J2EE

Cause:
The target of the ejb-link could not be found in the application.

Action:
Fix the ejb-link to point to a valid EJB.

BEA-160104
Invalid local reference in application {0}. A local reference from module {1} to {2} is not allowed because the referencing module does not have visibility to the classes of the referenced module.

Category:
J2EE

Cause:
The current module does not have visibility to the classloader of the EJB being referenced.

Action:
Look at the classloader organization defined by the classloader-structure element in weblogic-application.xml and ensure that the calling module is either using the same classloader as the module containing the referenced EJB or that the calling module is using a classloader that is an offspring of the classloader of the EJB module.

BEA-160106
ERROR: The source file, "{0}", could not be found.

Category:
J2EE

Cause:
The source file could not be found.

Action:
Ensure that the specified source file exists and try again.

BEA-160108
ERROR: Error accessing input file "{0}": {1}

Category:
J2EE

Cause:
The source file could not be accessed.

Action:
Ensure that the source file is accessible and try again.

BEA-160109
ERROR: Error copying files to the directory "{0}": {1}

Category:
J2EE

Cause:
The compiler was unable to extract the source archive to a directory. This can be caused by a lack of permission to write to the directory or a lack of disk space.

Action:
Ensure that the directory is writable and that there is enough free disk space to extract the archive. Alternatively, manually extract the archive to a directory and specify the directory name as the appc argument instead of the archive.

BEA-160110
ERROR: appc could not create the working directory, "{0}". Ensure that this directory can be created and try again.

Category:
J2EE

Cause:
A directory was specified in the appc command and it could not be created. appc will not be able to finish compiling the application because of this.

Action:
Ensure that the directory can be created and try again.

BEA-160111
ERROR: appc can not write to the working directory, "{0}". Ensure that you have write permission for this directory and try again.

Category:
J2EE

Cause:
The specified directory is not writable.

Action:
Ensure that the directory is writable and try again.

BEA-160112
Error: The directory, "{0}", does not contain a valid module. If the directory represents an EAR file, it must contain a META-INF/application.xml file. If the directory represents an ejb-jar file, it must contain a META-INF/ejb-jar.xml file. If the directory represents a WAR file, it must contain a WEB-INF/web.xml file. Ensure that the source directory is a valid module and try again.

Category:
J2EE

Cause:
The specified directory does not contain a valid module to compile.

Action:
Ensure that the specified source directory contains a valid module and try again.

BEA-160113
Error: The source file, "{0}", is not a valid ejb-jar file. To be valid, it must contain a META-INF/ejb-jar.xml file.

Category:
J2EE

Cause:
The specified source file is not a valid ejb-jar file.

Action:
Ensure that the specified source file is a valid ejb-jar file and try again.

BEA-160114
Error: The source file, "{0}", is not a valid WAR file. To be valid, it must contain a WEB-INF/web.xml file.

Category:
J2EE

Cause:
The specified source file is not a valid WAR file.

Action:
Ensure that the specified source file is a valid WAR file and try again.

BEA-160115
Error: The source file, "{0}", is not a valid EAR file. To be valid, it must contain a META-INF/application.xml file.

Category:
J2EE

Cause:
The specified source file is not a valid EAR file.

Action:
Ensure that the specified source file is a valid EAR file and try again.

BEA-160117
appc is unable to continue processing file "{0}": {1}

Category:
J2EE

Cause:
An error occurred while processing the specified source file.

Action:
Find the cause of the exception and take any necessary steps to remedy it.

BEA-160118
appc is unable to continue processing the file "{0}". The following error occurred while accessing it: {1}

Category:
J2EE

Cause:
An error occurred while processing the specified source file.

Action:
Find the cause of the exception and take any necessary steps to remedy it.

BEA-160119
appc is unable to process the file "{0}". The following error occurred: {1}

Category:
J2EE

Cause:
An error occurred while processing the specified source file.

Action:
Find the cause of the exception and take any necessary steps to remedy it.

BEA-160120
Error: The module, "{0}", is declared either in the application.xml or in the weblogic-application.xml descriptor but cannot be found in the EAR file.

Category:
J2EE

Cause:
The specified module cannot be found in the EAR file.

Action:
Ensure that either the application.xml or the weblogic-application.xml declaration is correct.

BEA-160121
Errors encountered while compiling module "{0}": {1}

Category:
J2EE

Cause:
Errors were encountered while compiling the specified module.

Action:
Investigate the specific errors and take any recommended actions.

BEA-160122
Errors validating EAR file: {0}

Category:
J2EE

Cause:
Errors were encountered while validating the EAR file.

Action:
Investigate the specific errors and take any recommended actions.

BEA-160123
ERROR: Could not create output archive, "{0}", restoring previous archive. The error was: {1}

Category:
J2EE

Cause:
An error occurred while creating the output archive.

Action:
Investigate the specific error and take any necessary actions.

BEA-160124
ERROR: Could not create output archive "{0}". The error was: {1}

Category:
J2EE

Cause:
An error occurred while creating the output archive.

Action:
Investigate the specific error and take any necessary actions.

BEA-160125
ERROR: Could not delete old backup file: {0}.

Category:
J2EE

Cause:
An old backup file could not be removed.

Action:
Determine why the old backup file could not be deleted and remedy the problem. Manually deleting the old backup file prior to running appc should fix this issue.

BEA-160126
ERROR: Could not create backup file "{0}". The error was: {1}

Category:
J2EE

Cause:
The specified backup file could not be created.

Action:
Determine why the backup file could not be created and remedy the problem. In particular, ensure that you have write permission to the specified file and that the disk is not full.

BEA-160127
ERROR: Could not delete previous archive: {0}

Category:
J2EE

Cause:
The specified archive could not be removed.

Action:
Determine why the archive could not be deleted and remedy the problem. In particular, ensure that you have permission to modify the specified file.

BEA-160128
ERROR: Incorrect appc command. Too many arguments were given. The appc command only takes a single argument, the source file, in addition to the supported options.

Category:
J2EE

Cause:
Too many arguments were specified in the appc command.

Action:
Correct the command and try again.

BEA-160129
ERROR: The alt-dd "{0}", specified for application module "{1}", could not be found. Remove the alt-dd entry from the application.xml descriptor or ensure that it points to a valid deployment descriptor.

Category:
J2EE

Cause:
The specified alt-dd could not be found.

Action:
Remove the invalid alt-dd entry from application.xml or ensure that it points to a valid deployment descriptor.

BEA-160130
ERROR: The application level alt-dd "{0}", specified in the appc command, could not be found. Ensure that the alt-dd points to a valid deployment descriptor or remove it from the command line.

Category:
J2EE

Cause:
The specified alt-dd could not be found.

Action:
Correct or remove the invalid alt-dd setting in the appc command.

BEA-160132
Warning: The {0} "{1}" for EJB "{2}" in the module "{3}" has an ejb-ref-type of {4} but the ejb-link does not resolve to an EJB of that type. Ensure that the ejb-link and ejb-ref-type are correct.

Category:
J2EE

Cause:
The ejb-ref or ejb-local-ref resolves to an EJB of a different type than is declared in the ejb-ref.

Action:
Ensure that the ejb-ref or ejb-local-ref resolves to the correct EJB. Once this is verified, ensure that the ejb-ref-type declared in the ejb-ref corresponds to the type of EJB being referred to.

BEA-160133
Warning: The {0} "{1}" in the module "{2}" has an ejb-ref-type of {3} but the ejb-link does not resolve to an EJB of that type. Ensure that the ejb-link and ejb-ref-type are correct.

Category:
J2EE

Cause:
The ejb-ref or ejb-local-ref resolves to an EJB of a different type than is declared in the ejb-ref.

Action:
Ensure that the ejb-ref or ejb-local-ref resolves to the correct EJB. Once this is verified, ensure that the ejb-ref-type declared in the ejb-ref corresponds to the type of EJB being referred to.

BEA-160134
Error: The EJB with the name "{0}" in ear module "{1}" has an entity-cache-ref with the name "{2}" in its weblogic-ejb-jar.xml descriptor but no application level entity cache with that name is defined in the weblogic-application.xml descriptor for the application.

Category:
J2EE

Cause:
The entity-cache referred to by the EJB could not be found.

Action:
Ensure that the entity-cache-ref is correct in the weblogic-ejb-jar.xml descriptor for the EJB. Also, ensure that an entity-cache with the same name is declared in the weblogic-application.xml descriptor for the application.

BEA-160137
Error: The message-destination-link "{0}" declared in the message-destination-ref "{1}" in the application module "{2}" could not be resolved. The target message-destination for the message-destination-ref could not be found. Ensure that the link is correct.

Category:
J2EE

Cause:
The target of the message-destination-link could not be found in the application.

Action:
Fix the message-destination-link to point to a valid message-destination.

BEA-160138
Could not set active version state for application: {0}.

Category:
J2EE

Cause:
See the message detail.

Action:
Contact My Oracle Support.

BEA-160139
The following library reference has "context-path" set, which has no effect when referencing a {1} library: {0}.

Category:
J2EE

Cause:
The library reference has "context-path" set, but is not referencing a WAR library.

Action:
Remove "context-path" from the library reference.

BEA-160140
Unresolved optional package references (in META-INF/MANIFEST.MF): {0}. Ensure that the referenced optional package has been deployed as a library.

Category:
J2EE

Cause:
One or more MANIFEST.MF files contain references to optional packages (using the Extension-List attribute). One or more of the referenced optional packages are not available.

Action:
Register the required optional packages or remove the reference(s) from the manifest(s).

BEA-160141
Could not initialize the library {0}. Ensure that the deployment unit is a valid library type (WAR, EJB, EAR, plain JAR). {1}

Category:
J2EE

Cause:
Refer to the exception in the message body.

Action:
Examine the stack trace.

BEA-160142
The library at {0} has an illegal Specification-Version: {1}. The Specification-Version must be a valid version string: int(.int)*, int >=0; for example: 2.1.1

Category:
J2EE

Cause:
The Specification-Version for the library at {0} cannot be parsed.

Action:
Fix the library Specification-Version to conform to the required version string syntax.

BEA-160143
Library {0} has an illegal Specification-Version: {1}. The Specification-Version must be a valid version string: int(.int)*, int >=0. For example: 2.1.1.

Category:
J2EE

Cause:
The library cannot be statically deployed because its MBean has an invalid Specification-Version.

Action:
Undeploy the library and deploy it again with a correct Specification-Version.

BEA-160144
Failed to register library {0}: {1}

Category:
J2EE

Cause:
The error is: {1}

Action:
Examine the error message.

BEA-160145
Failed to deploy library {0}, because of conflicting library Manifest values, and library information registered with the server: {1}. Check the library MANIFEST.MF file and correct version information there to match server settings, or undeploy the misconfigured library.

Category:
J2EE

Cause:
Conflict between library manifest values and library settings in the LibraryMBean.

Action:
Check the library MANIFEST.MF file and correct the version information there to match server settings, or undeploy the misconfigured library.

BEA-160146
Failed to process library at {0}, because of conflicting library manifest values and the library information provided on the appc command line: {1}.

Category:
J2EE

Cause:
There was a conflict between the library manifest values and the library information provided on the appc command line.

Action:
Avoid setting the library name and version information on the appc command line if its already set in the manifest or remove values from the manifest and set them on the appc command line.

BEA-160147
One or more libraries could not be processed. See error above.

Category:
J2EE

Cause:
See error above.

Action:
See error above.

BEA-160148
These libraries were not referenced by the compiled application: {0}.

Category:
J2EE

Cause:
The compiled application did not reference the libraries that were passed to appc.

Action:
These libraries do not need to be passed to appc to compile this particular application.

BEA-160149
Error while processing library references. {0}

Category:
J2EE

Cause:
The application has library references that do not resolve.

Action:
Ensure that the library references are accurate and that the required libraries are available.

BEA-160150
A library reference in weblogic-application.xml has an illegal Specification-Version: {0}. The Specification-Version must be a valid version string: int(.int)*, int >=0; example: 2.1.1

Category:
J2EE

Cause:
The Specification-Version of a library reference in weblogic-application.xml cannot be parsed.

Action:
Fix the library Specification-Version in weblogic-application.xml to conform to the required version string syntax.

BEA-160151
Registered library {0}.

Category:
J2EE

Cause:
Library registration was successful.

Action:
No action is required.

BEA-160152
The library at {0} was not recognized as a valid library type.

Category:
J2EE

Cause:
The library at {0} was not recognized as a valid library type.

Action:
Ensure that the library is one of the supported library types.

BEA-160153
Error while cleaning up library {0}: {1}

Category:
J2EE

Cause:
Error while cleaning up library {0}: {1}

Action:
Examine the stack trace.

BEA-160154
Error while cleaning up library: {0}. {1}

Category:
J2EE

Cause:
Error while cleaning up library: {0}. {1}

Action:
Examine the stack trace.

BEA-160155
Cannot find library at: {0}.

Category:
J2EE

Cause:
{0} is not a file.

Action:
Fix the path to the library.

BEA-160156
Cannot process libdir: {0} is not a directory.

Category:
J2EE

Cause:
{0} is not a directory.

Action:
Fix the path to libdir.

BEA-160157
The referenced library, {0}, is not a supported application library.

Category:
J2EE

Cause:
{0} is not a supported application library.

Action:
Remove the reference to library {0} from weblogic-application.xml.

BEA-160158
Ignoring Extension-List reference {0}, because the manifest does not have an entry for {0}-Extension-Name. The manifest is at {1}/META-INF/MANIFEST.MF

Category:
J2EE

Cause:
A declared Extension-List name does not have the required Extension-Name entry.

Action:
Remove {0} from the Extension-List or add {0}-Extension-Name entry into the manifest.

BEA-160159
Bad optional package reference in manifest at {2}/META-INF/MANIFEST.MF, for optional package with Extension-Name: {0}. Illegal Specification-Version: {1}. The Specification-Version must be a valid version string: int(.int)*, int >=0; example: 2.1.1. Ignoring this Optional Package reference.

Category:
J2EE

Cause:
Cannot parse the Specification-Version of an optional package reference.

Action:
Change the optional package reference Specification-Version to the required version string syntax.

BEA-160161
Error while parsing the application descriptors for {0}: {1}.

Category:
J2EE

Cause:
The cause is {1}

Action:
Examine the error message.

BEA-160162
No META-INF/application.xml was found in the EAR at {0}.

Category:
J2EE

Cause:
The application.xml file could not be found.

Action:
Ensure that the path to the EAR file is correct and add the missing application.xml.

BEA-160163
No modules were found in application.xml for EAR: {0}. Nothing to do.

Category:
J2EE

Cause:
There are no modules in this EAR's application.xml

Action:
Add module entries to the EAR's application.xml.

BEA-160164
Error while importing library {0}: {1}

Category:
J2EE

Cause:
See the exception: {1}.

Action:
Examine the stack trace.

BEA-160165
The EAR library at {0} is organized using the splitdir directory structure. splitdir is not supported for libraries.

Category:
J2EE

Cause:
splitdir is not supported for EAR libraries.

Action:
Archive this library. If a build file was generated using BuildXMLGen, run the EAR target in that file.

BEA-160166
References were found in the deployment plan for module "{0}" with URI, "{1}". The plan was merged.

Category:
J2EE

Cause:
This is an informational message.

Action:
No action is required.

BEA-160167
The module {1} in application {0} uses ejb-links but no EJB modules were found for this application.

Category:
J2EE

Cause:
The ejb-links must correspond to an EJB module deployed within the same application.

Action:
Ensure that the EJB modules to which you intended to link exist and have been configured properly.

BEA-160168
An error occurred while merging descriptors: {0}

Category:
J2EE

Cause:
An error occurred while merging descriptors. Check the stack trace.

Action:
Check the stack trace.

BEA-160169
An error occurred while parsing descriptors: {0}

Category:
J2EE

Cause:
An error occurred while parsing descriptors.

Action:
Check the stack trace.

BEA-160170
Imported library {0} for Application {1}

Category:
J2EE

Cause:
This is an information message.

Action:
No action is required.

BEA-160171
ERROR: The plan file, "{0}", could not be found.

Category:
J2EE

Cause:
The plan file could not be found.

Action:
Ensure that the specified plan file exists and try again.

BEA-160172
ERROR: To run appc, specify a plan file ending with the suffix .xml.

Category:
J2EE

Cause:
The plan file type is not supported.

Action:
Correct the plan argument and try again.

BEA-160173
ERROR: Error accessing input file "{0}": {1}

Category:
J2EE

Cause:
The plan file could not be accessed.

Action:
Ensure that the plan file is accessible and try again.

BEA-160174
ERROR: Failed to parse deployment plan "{0}": {1}

Category:
J2EE

Cause:
The plan file could not be parsed.

Action:
Resolve parse errors in the plan and retry.

BEA-160175
ERROR: Could not find JMS module of name "{2}" specified in the resource-link named "{3}" in the "{1}" component named "{0}".

Category:
J2EE

Cause:
The JMS module used in the resource-link cannot be found in the application package.

Action:
Package the missing JMS module as part of this application and retry.

BEA-160176
ERROR: Could not find the JMS resource named "{4}" of type "{5}" inside the JMS module "{2}" that is specified in the resource-link named "{3}" in the "{1}" component named "{0}".

Category:
J2EE

Cause:
The JMS resource used in th resource-link was not found in the application package.

Action:
Create the missing JMS resource in the corresponding JMS module and retry.

BEA-160177
The application at "{0}" was not recognized as a valid application type. If this is an EAR file, please ensure the META-INF/application.xml exists. EJB-JARs should have a META-INF/ejb-jar.xml or corresponding annotations exist. If this is an exploded WAR, the name of directory must be end with ".war". RARs require a META-INF/ra.xml. A JMS deployment should be an XML file whose name ends with "-jms.xml". A JDBC deployment should be an XML file whose name ends with "-jdbc.xml". For other application types, consult the WebLogic Server documentation.

Category:
J2EE

Cause:
The application was not a valid J2EE application.

Action:
Correct the application and try again.

BEA-160180
An error was encountered and ignored while rolling back an update to application {0}. The error was: {1}

Category:
J2EE

Cause:
See the included error message.

Action:
Correct the application based on the reported error.

BEA-160181
An error was encountered and ignored during undeployment. The error was: {0}

Category:
J2EE

Cause:
See the included error message.

Action:
Correct the application based on the reported error.

BEA-160182
An error was encountered and ignored during transition to administration mode. The error was: {0}

Category:
J2EE

Cause:
See the included error message.

Action:
Correct the application based on the reported error.

BEA-160183
Unable to find the jar-uri: {1} specified for the ApplicationLifecycleListener, Startup, or Shutdown class in the weblogic-application.xml of application: {0}.

Category:
J2EE

Cause:
The JAR URI is incorrect or the file does not exist or cannot be read.

Action:
Correct the application based on the reported error.

BEA-160184
ERROR: Could not find JDBC module of name "{2}" specified in the resource-link named "{3}" in the "{1}" component named "{0}".

Category:
J2EE

Cause:
The JDBC module used in the resource-link was not found in the application package.

Action:
Package the missing JDBC module as part of this application and retry.

BEA-160185
ERROR: Could not find the JDBC resource named "{4}" of type "{5}" inside the JDBC module "{2}" that is specified in the resource-link named "{3}" in the "{1}" component named "{0}".

Category:
J2EE

Cause:
The JDBC resource used in the resource-link was not found in the application package.

Action:
Create the missing JDBC resource in the corresponding JDBC module and retry.

BEA-160186
Compiling EAR module "{0}"

Category:
J2EE

Cause:
This is an informational message.

Action:
No action is required.

BEA-160187
weblogic.appc failed to compile the application. Recompile with the -verbose option for more details about the issue.

Category:
J2EE

Cause:
Compilation can fail for many reasons. See the specific error message for details.

Action:
Use the provided error message to track down and fix the problem.

BEA-160188
{0}.

Category:
J2EE

Cause:
The application has library references that do not resolve.

Action:
Ensure that the library references are accurate and that the required libraries are available.

BEA-160189
There are no modules in the application that match URIs: {0}. Note that for Web applications, you should specify the context-root rather than the web-uri.

Category:
J2EE

Cause:
The specified URIs were not found in the running application.

Action:
Specify the correct URIs which are typically found in your application's META-INF/application.xml.

BEA-160191
While upgrading weblogic.xml, the server encountered "{1}" parameter "{0}". This parameter has been deprecated and will be removed

Category:
J2EE

Cause:
This is a deprecated parameter.

Action:
Remove the deprecated parameter from the weblogic.xml deployment descriptor.

BEA-160192
While upgrading weblogic.xml, the server encountered "{1}" parameter "{0}". This parameter is unknown and will be removed

Category:
J2EE

Cause:
The parameter is not defined in the schema.

Action:
Check the weblogic.xml deployment descriptor and remove the parameter.

BEA-160193
Error: The source file, "{0}", is not a valid RAR file. To be valid, it must contain a META-INF/ra.xml file.

Category:
J2EE

Cause:
The specified source file is not a valid RAR file.

Action:
Ensure that the specified source file is a valid RAR file and try again.

BEA-160194
The following modules cannot be started because they are already running: {0}.

Category:
J2EE

Cause:
The specified modules are already running.

Action:
Remove the specified modules from the list of modules to partially stop.

BEA-160195
The application version lifecycle event listener {1} is ignored because the application {0} is not versioned.

Category:
J2EE

Cause:
The application is not a versioned application.

Action:
If the application is deployed as a non-versioned application in error, undeploy the current application and deploy it as a versioned application. If the application version lifecycle listener is specified in error, remove it from the application or specify a non-versioned application lifecycle listener.

BEA-160196
Unable to find the jar-uri: {1} specified for the Singleton class in the weblogic-application.xml of application: {0}

Category:
J2EE

Cause:
The JAR URI is incorrect or the file does not exist or cannot be read.

Action:
Correct the application based on the reported error.

BEA-160197
Unable to load descriptor {1} of module {0}. The error is {2}.

Category:
J2EE

Cause:
The descriptor is not valid.

Action:
Correct the descriptor based on the reported error.

BEA-160198
Error: The ejb-ref "{3}" configured via an @EJB annotation in the module "{0}" is linked to the EJB "{1}". However, the EJB "{1}" does not declare the interface "{2}", as specified by the @EJB annotation. Ensure that the ejb-ref is linked to the correct bean and that the target bean declares the interface specified by the ejb-ref.

Category:
J2EE

Cause:
The @EJB has an incorrect beanName (ejb-link) attribute or the target bean must implement the interface declared by the @EJB annotation.

Action:
Ensure that the ejb-ref is linked to the correct bean and that the target bean declares the interface specified by the ejb-ref.

BEA-160199
Error resolving ejb-ref "{0}" from module "{1}" of application "{2}". The ejb-ref does not have an ejb-link and the JNDI name of the target Bean has not been specified.

Category:
J2EE

Cause:
Attempts to automatically link the ejb-ref to its target Bean failed because multiple EJBs in the application were found to implement the "{3}" interface, including {4}.

Action:
Specify a qualified ejb-link for this ejb-ref to indicate which EJB is the target of this ejb-ref.

BEA-160200
Error resolving ejb-ref "{0}" from module "{1}" of application "{2}". The ejb-ref does not have an ejb-link and the JNDI name of the target bean has not been specified. Attempts to automatically link the ejb-ref to its target bean failed because no EJBs in the application were found to implement the "{3}" interface. Link or map this ejb-ref to its target EJB and ensure the interfaces declared in the ejb-ref are correct.

Category:
J2EE

Cause:
See the error message for details.

Action:
Link or map this ejb-ref to its target EJB and ensure the interfaces declared in the ejb-ref are correct.

BEA-160201
Error resolving ejb-ref "{0}" from module "{1}" of application "{2}". The ejb-ref specifies an ejb-link but the target bean does not implement the interface "{3}" as specified in the ejb-ref declaration. Ensure that the ejb-link and interface name(s) declared in the ejb-ref are correct.

Category:
J2EE

Cause:
See the error message for details.

Action:
Ensure that the ejb-link and interface name(s) declared in the ejb-ref are correct.

BEA-160202
You have specified a {1} setting in your configuration for persistence unit {0}. This setting will be ignored and all log messages will be sent to the WebLogic Server logging subsystem. Trace-level logging is controlled by the various JPA-specific debug settings in config.xml, or through the WebLogic Server Administration Console.

Category:
J2EE

Cause:
Persistence unit configuration specifies logging information, but WebLogic Server will ignore this information.

Action:
Remove the {1} setting from persistence unit {0}.

BEA-160203
You have specified a {1} setting in your configuration for persistence unit {0}. This value will be replaced with {1}.

Category:
J2EE

Cause:
The persistence unit configuration specifies ID information, but WebLogic Server will ignore this information.

Action:
Remove the {1} setting from persistence unit {0}.

BEA-160204
The ApplicationLifecycleListener "{1}" of application "{0}" has a run-as user configured with the principal name "{2}" but a principal of that name could not be found. Ensure that a user with that name exists.

Category:
J2EE

Cause:
The run-as principal configured for this ApplicationLifecycleListener does not exist in the security realm.

Action:
Ensure that the user exists or choose another principal for the run-as configuration.

BEA-160205
The ApplicationLifecycleListener "{1}" of application "{0}" has a run-as user configured with the principal name "{2}" but a principal of that name has higher privileges than the user performing the deployment. As a result, this deployment user cannot perform the current deployment action. Try the deployment action with an administrative privileged user.

Category:
J2EE

Cause:
Higher run-as privileges are needed to deploy an ApplicationLifecycleListener in this situation.

Action:
Try the deployment action with an administrative privileged user.

BEA-160207
Error autowiring ejb-ref "{0}" from module "{1}" of application "{2}". The ejb-ref does not specify an interfaceName but multiple interfaces on the target bean were found. Specify a beanInterface to indicate which EJB is the target for ejb-ref "{0}".

Category:
J2EE

Cause:
There was a problem resolving the target of the specified ejb-ref.

Action:
Specify a beanInterface to indicate which EJB is the target.

BEA-160210
ERROR: The moduleUri, "{0}", could not be found.

Category:
J2EE

Cause:
The moduleUri could not be found.

Action:
Ensure that the specified moduleUri exists and try again.

BEA-160211
Waiting for ExecuteQueue {0} to finish {1} pending requests

Category:
J2EE

Cause:
The server found pending requests in one of the execute queues while suspending. The server will wait for the requests to complete.

Action:
No action is required.

BEA-160212
This is an unexpected exception.

Category:
J2EE

Cause:
See the message detail.

Action:
No action is required.

BEA-160213
This directory contains internal files used by the deployment system. Contents of this directory should never be removed while the corresponding server is running. Removing sub-directories when the server is down will slow down the subsequent deployment of the corresponding applications because these sub-directories need to be created again. The individual sub-directories are removed when the corresponding application is undeployed.

Category:
J2EE

Cause:
See the message detail.

Action:
No action is required.

BEA-160214
Output location exists {0}

Category:
J2EE

Cause:
The file pointed to by the output location already exists,

Action:
No action is required.

BEA-160215
ERROR: The moduleUri, "{0}", is not Web module.

Category:
J2EE

Cause:
The moduleUri is not valid Web module.

Action:
Ensure that the specified moduleUri is a valid Web module and try again.

BEA-160216
Unexpected errors occurred while sending deployment event {1} on behalf of application "{0}".

Category:
J2EE

Cause:
The deployment event listener(s) registered to receive deployment event caused unexpected exceptions when processing deployment event {1} on behalf of application "{0}".

Action:
Report this problem to My Oracle Support.

BEA-160217
Unexpected errors occurred while sending a vetoable deployment event on behalf of application "{0}".

Category:
J2EE

Cause:
The deployment event listener(s) registered to receive vetoable deployment events caused unexpected exception(s) when processing deployment event {1} on behalf of application "{0}".

Action:
Report this problem to My Oracle Support.

BEA-160218
Filtering classloader configuration ignored for module {1} of application {0}

Category:
J2EE

Cause:
Filtering classloader configuration is only supported in descriptors at the main level of the deployment (for example, in enterprise applications or standalone Web applications). Such configuration is not supported in modules of an enterprise application.

Action:
Remove the filtering classloader configuration from the deployment descriptor of module {1} of application {0}.

BEA-160219
The JPA persistence unit {0} will use the following configured default persistence provider: {1}

Category:
J2EE

Cause:
No provider element was specified in the associated persistence.xml file.

Action:
No action is required unless you want a different JPA provider to be used for the given persistence unit, in which case you can specify the provider in the persistence.xml file or change the default provider for the domain.

BEA-160220
Compilation completed successfully.

Category:
J2EE

Cause:
The compilation task has completed successfully.

Action:
No action is required.

BEA-160221
env-entry for type java.lang.Character had length = 0.

Category:
J2EE

Cause:
See the error message body.

Action:
See the error message body.

BEA-160222
Could not create a new JMS ConnectionFactory for the application: {0}.

Category:
J2EE

Cause:
See the error message body.

Action:
See the error message body.

BEA-160223
The resource-env-ref "{0}" declared in the standard descriptor or annotation has no JNDI name mapped to it. The resource-env-ref must be mapped to a JNDI name using the resource-env-description element of the weblogic proprietary descriptor or corresponding annotation.

Category:
J2EE

Cause:
See the error message body.

Action:
See the error message body.

BEA-160224
Encountered an error cleaning up references for application: ${0} - ${1}

Category:
J2EE

Cause:
See the error message body.

Action:
See the error message body.

BEA-160225
A new JPA API method is being invoked against an older version of the persistence provider, in which the method is not supported yet. Update the application to use a compliant provider, or ensure that the application does not attempt to invoke unsupported methods that are not supported by the current provider.

Category:
J2EE

Cause:
A new JPA API method is being invoked against an older version of the persistence provider, in which the method is not supported yet.

Action:
Update the application to use a compliant provider, or ensure that the application does not attempt to invoke unsupported methods that are not supported by the current provider.

BEA-160226
Ignoring the configuration file [{0}: {1}]. Only applications that use Kodo as the JPA provider can be configured with this file.

Category:
J2EE

Cause:
This file can configure only persistence units that use Kodo.

Action:
Remove the configuration file or specify the information in persistence.xml; otherwise, one or more persistence units in this application use Kodo.

BEA-160227
The persistence unit "{0}" in "{1}" does not use Kodo as a JPA provider. Ignoring the configuration for this persistence unit found in persistence-configuration.xml.

Category:
J2EE

Cause:
The persistence-configuration.xml file cannot configure persistence units that do not use Kodo.

Action:
Remove the persistence unit from the persistence-configuration.xml file or specify in persistence.xml, or otherwise, that the persistence unit uses Kodo.

BEA-160228
AppMerge failed to merge your application. If you are running AppMerge on the command-line, merge again with the -verbose option for more details. See the error message(s) below.

Category:
J2EE

Cause:
AppMerge can fail for many reasons. See the specific error message for details.

Action:
Use the provided error message to track down and fix the problem.

BEA-160229
Ignoring plan file {0} as does not exist.

Category:
J2EE

Cause:
Either the plan specified is not a file or the plan file does not exist.

Action:
Use the provided error message to track down and fix the problem.

BEA-160230
Created working directory: {0}

Category:
J2EE

Cause:
This is an informational message.

Action:
No action is required.

BEA-160231
Unable to identify application type for {0}

Category:
J2EE

Cause:
The source file type may not be supported.

Action:
Use the provided error message to track down and fix the problem.

BEA-160232
Unable to identify module type for {0}

Category:
J2EE

Cause:
The module specified in the application descriptor may not be supported.

Action:
Use the provided error message to track down and fix the problem.

BEA-160233
Unable to identify module type {0}

Category:
J2EE

Cause:
A module specified in the application descriptor may not be supported.

Action:
Use the provided error message to track down and fix the problem.

BEA-160238
The message-destination {0} declared in the deployment descriptor or by annotation does not have a corresponding message-destination-descriptor element in the weblogic deployment descriptor or corresponding annotation. Alternatively, mapped-name or lookup-name of message-destination can be specified for the destination.

Category:
J2EE

Cause:
A declared message-destination is not mapped correctly.

Action:
Map the declared message-destination to the actual message destination using the message-destination-descriptor element in the weblogic deployment descriptor, or specify mapped-name or lookup-name of message-destination.

BEA-160239
Conflicting environment entry {0}, name is {1}.

Category:
J2EE

Cause:
Multiple entries have the same environment entry name, but have different values.

Action:
Ensure that each environment entry has a different environment name, or that entries with the same have identical values.

BEA-160240
The resource-ref "{0}" declared in the standard descriptor or annotation has no JNDI name mapped to it. The resource-ref must be mapped to a JNDI name using the resource-description element of the weblogic proprietary descriptor or corresponding annotation.

Category:
J2EE

Cause:
See the error message for details.

Action:
See the error message for details.

BEA-160241
Error: There are validation errors for environment entries in module {0}. {1}

Category:
J2EE

Cause:
There are validation errors in the environment entries. With an EJB in WAR files, it is possible that names for environment entries may clash. Care must be taken by the deployer or application assembler to avoid these name collisions, as they can cause the application to fail. An environment entry that is declared in the application.xml descriptor must specify a JNDI name in the java:app or java:global namespace.

Action:
Correct the validation errors.

BEA-160242
Warning: Data source definition {0} in interceptor {1} may have been overwritten by EJB component in module {2}, ignored.

Category:
J2EE

Cause:
The EJB component may have overwritten data source definitions in its interceptors. In this case, data source definitions in interceptors will be ignored.

Action:
Please verify the cause above is not an issue for the application.

BEA-160243
A creating StoredProcedureQuery API method is being invoked on a container-managed and transaction-scoped EntityManager outside of a transaction, but the method is not supported yet. Update the application to start a transaction before creating the StoredProcedureQuery objects.

Category:
J2EE

Cause:
A creating StoredProcedureQuery API method is being invoked on a container-managed and transaction-scoped EntityManager outside of a transaction, but the method is not supported yet.

Action:
Update the application to start a transaction before creating the StoredProcedureQuery objects.

BEA-160244
An environment entry {0} declared in the application.xml descriptor does not specify a JNDI name in the java:app or java:global namespace.

Category:
J2EE

Cause:
An environment entry declared in the application.xml descriptor must specify a JNDI name in the java:app or java:global namespace.

Action:
Specify a JNDI name in the java:app or java:global namespace.

BEA-160245
It is an error for both the env-entry-value and lookup-name elements to be specified for a given env-entry element {0}.

Category:
J2EE

Cause:
An environment entry declared in the application.xml descriptor specified both the env-entry-value and lookup-name elements.

Action:
Specify either the env-entry-value or lookup-name, but not both.

BEA-160246
Warning: It is an error to request injection of two resources into the same target class {0} and target name {1}.

Category:
J2EE

Cause:
Injection of two resources into the same target was requested.

Action:
Remove one of the targets from the application.

BEA-160247
Warning: Ignore the realm name: {0} in deployment descriptor.

Category:
J2EE

Cause:
The realm name was ingored in the deployment descriptor.

Action:
No action is required.

BEA-160248
Unable to parse class file: {0}. {1}

Category:
J2EE

Cause:
This is generally due to a corrupted class file in the application.

Action:
Use an external tool such as JAD to ascertain the validity of the class. It is important to fix any invalid class in order to avoid potentially severe errors later in deployment or at runtime.

BEA-160249
Skipping schema-generation actions for persistence unit {0} by overriding relevant properties because this is only a server startup instead of an application deployment.

Category:
J2EE

Cause:
This is an information message.

Action:
No action is required.

BEA-160250
No ComponentMBeanFactory with the class name {0} was found among the registered DeploymentFactory instances. Creating an instance using reflection.

Category:
J2EE

Cause:
There was no registered DeploymentFactory instance that had the same name as {0}.

Action:
No action is required.

BEA-160251
Failed to create an instance of ComponentMBeanFactory with the class name {0} because of an exception {1}

Category:
J2EE

Cause:
The ComponentMBeanFactory instance could not be located among registered DeploymentFactory instances.

Action:
No action is required.

BEA-160252
The following application inconsistencies must be corrected {0}. Code path: {1}

Category:
J2EE

Cause:
WebLogic Server detected multiple declarations of the same env-entry.

Action:
Search the application, including any shared library, for the listed env-entry declarations in both the descriptors and code annotations. Make sure that all the declarations are consistent. It is better to declare each env-entry only once to avoid this issue.

BEA-160253
{0}

Category:
J2EE

Cause:
See the message ddetails.

Action:
Consider eliminating redundant declarations of entries to avoid potential conflicts.

BEA-160254
Unable to read from application cache file {0} because of exception {2} with message: {1}

Category:
J2EE

Cause:
The cause of this exception is an underlying Java exception.

Action:
No action is needed, since WebLogic can recover from this failure by constructing these objects again.

BEA-160255
Unable to write to application cache file {0} because of exception message: {1}

Category:
J2EE

Cause:
The cause of this exception is an underlying Java IOException.

Action:
No action is needed, since WebLogic can recover from this failure by constructing these objects again when it need to read from this location.

BEA-160256
Unable to close {1} object stream to application cache file {0} because of exception message: {2}

Category:
J2EE

Cause:
The cause of this exception is an underlying Java IOException.

Action:
No action is needed, since WebLogic can recover from this failure.

BEA-160257
Application with name "{0}" cannot be deployed because the name is already in use in {1} named "{2}".

Category:
J2EE

Cause:
The deployment failed due to another application or library that already exists with the same name in the current deployment scope.

Action:
Retry the deployment with a different application name.

BEA-160258
The multi-version file {0} is expected to be a directory

Category:
J2EE

Cause:

Action:
Correct the file format

BEA-160259
The version directory {0} is expected to be named in a dot-decimal format

Category:
J2EE

Cause:
The name format is incorrect

Action:
Correct the directory name

BEA-160260
No valid version found in multi-version directory {0}

Category:
J2EE

Cause:
No valid version exists in the multi-version directory

Action:
Add a valid version to the directory

BEA-160261
Exception in application {0}, marked to be in MultiVersionFormat. The application is located at {1}. The exception is {2}

Category:
J2EE

Cause:
{2}

Action:
Please correct the underlying problem represented by {2}

BEA-160262
The application version is "{0}"

Category:
J2EE

Cause:
This is an informational message giving the hash version of an application using the appmerge tool

Action:
None

BEA-160263
The files included in the application hash are {0}

Category:
J2EE

Cause:
This is an informational message giving the names of the files included in the version hash in the appmerge tool

Action:
None

BEA-169800
A PooledConnectionFactory object with an invalid external version of {0} was found.

Category:
JMSPool

Cause:
The version of WebLogic Server that stored the PooledConnectionFactory object is not compatible with the version that is retrieving it.

Action:
Contact My Oracle Support.

BEA-169801
The JMS method {0} may not be called inside an EJB or servlet.

Category:
JMSPool

Cause:
The application code has violated the Java EE specifications.

Action:
Change the code to avoid calling the specified method.

BEA-169802
Cannot create a wrapped JMS connection using a username and password when the res-auth element is set to Container.

Category:
JMSPool

Cause:
The application code is not using the Java EE APIs properly.

Action:
Either remove the username and password, or set the res-auth element to Application.

BEA-169803
JNDI lookup of the JMS connection factory {0} failed

Category:
JMSPool

Cause:
The remote JNDI server or JMS server is not available, or the name was incorrectly specified.

Action:
Check that the server is running, and check the name in the deployment descriptor XML files.

BEA-169804
Cannot use a JMS connection factory because the object is of the wrong type.

Category:
JMSPool

Cause:
Either the name of the connection factory in the deployment descriptor XML files is wrong, or the wrong object was bound into JNDI.

Action:
Check the name in the XML files against what is actually registered in JNDI.

BEA-169805
A pooled JMS connection is being closed because an exception was detected on the connection: {0}

Category:
JMSPool

Cause:
The JMS server is unavailable or there is some other problem with it that makes it impossible to send or receive messages.

Action:
Check the configuration parameters for the JMS server, and check that it is available on the network.

BEA-169806
Cannot use a JMS destination because the object is of the wrong type.

Category:
JMSPool

Cause:
Change the application to use a valid destination type.

Action:
Change the application to use a valid destination type.

BEA-169807
There was an error while making the initial connection to the JMS resource named {0} from within an EJB or a servlet. The server will attempt the connection again later. The error was {1}

Category:
JMSPool

Cause:
See the error message from the JMS provider.

Action:
No action is required.

BEA-169808
There was an error while making the initial connection to the JMS resource named {0} from the EJB "{1}" inside application "{2}". The server will attempt the connection again later. The error was {3}

Category:
JMSPool

Cause:
See the error message from the JMS provider.

Action:
No action is required.

BEA-169809
An error occurred while registering the JMS connection with JTA.

Category:
JMSPool

Cause:
The JMS connection factory specified does not properly support XA or something is wrong with the transaction system.

Action:
Check the linked exception and verify that the JMS provider properly supports XA.

BEA-169810
An error occurred while committing or rolling back a JTA transaction used for a JMS operation by the Java EE container

Category:
JMSPool

Cause:
There was a problem with the transaction system.

Action:
See the linked exception for more information.

BEA-169811
The JMS object may not be used because it has been closed.

Category:
JMSPool

Cause:
The object has been closed.

Action:
Fix the programming error.

BEA-169812
The pooled JMS session is enlisted in another transaction and may not be used elsewhere.

Category:
JMSPool

Cause:
Check the application code to ensure that a pooled JMS session (retrieved from the JNDI java:comp/env/jms context) is not kept between transactions. It should be closed so that it is returned to the pool.

Action:
Check the application code.

BEA-169813
There was an error while closing a JMS session pool or a pooled JMS connection: {0} The pool or object was forcibly closed.

Category:
JMSPool

Cause:
See the linked exception for more information.

Action:
No action is required.

BEA-169814
The JMS session pool has been disabled.

Category:
JMSPool

Cause:
An administrative action was taken.

Action:
Re-enable the session pool.

BEA-169815
A JMS session pool could not be created because the {0} property was not specified.

Category:
JMSPool

Cause:
A JMS session pool was either created directly by the user or by internal container code that did not properly specify a property.

Action:
Check for other log messages that give more information about the failure.

BEA-169816
The JMS session pool is shutting down.

Category:
JMSPool

Cause:
The pool is being shut down, possibly because of an error.

Action:
Check for other errors that indicate why the pool is being shut down and retry the operation.

BEA-169817
The JMS connection factory resource {0} declared in the EJB "{1}" as part of application "{2}" does not support XA. It cannot be used inside a transaction context.

Category:
JMSPool

Cause:
If the specified JMS connection factory is intended to be used inside a transaction context, then the EJB was configured improperly.

Action:
If the specified JMS connection factory is intended for use inside a transaction context, then the connection factory used by the EJB must be changed so that it supports XA, or the EJB descriptor must be changed to point to a different connection factory. However, if the connection factory will never be used inside a transaction context, then no action is necessary.

BEA-169818
The JMS connection pool named "{0}" has a configured connection factory JNDI name of "{1}". However, an object that is not a javax.jms.ConnectionFactory is bound to that JNDI name. The object bound to that JNDI name has type "{2}".

Category:
JMSPool

Cause:
An object other than a ConnectionFactory is bound to the configured JNDI name of the connection pool.

Action:
Either change the JNDI name of the JMS connection pool property or change the JNDI name of the object that is currently bound into JNDI.

BEA-169819
There was an error with a resource pool used to pool JMS sessions

Category:
JMSPool

Cause:
There is a problem with the resource pool.

Action:
See the linked exception for details.

BEA-169820
A JMS message consumer could not be created using a temporary queue or topic that was created using another connection.

Category:
JMSPool

Cause:
This is an application programming error.

Action:
Change the application code.

BEA-169821
Error creating or instantiating a wrapper for class {0}

Category:
JMSPool

Cause:
There may be an error with the classpath or with the underlying JMS provider's code.

Action:
Check the classpath. If this does not fix the problem, contact My Oracle Support.

BEA-169822
Unable to use a wrapped JMS session in the transaction because two-phase commit is not available.

Category:
JMSPool

Cause:
The JMS connection factory specified does not support two-phase commit.

Action:
For WebLogic Server JMS, two-phase commit may be enabled by setting the "UserTransactionsEnabled" flag on the JMS connection factory. For other JMS providers, you must specify a JMS connection factory that supports XA.

BEA-169823
Failure occured on createQueueConnection. Unexpected return type.

Category:
JMSPool

Cause:
Probable cause is the JMS 1.1 ConnectionFactory with the JMS 1.0.2 createQueueConnection() API. Some JMS providers do not support backward compatibility.

Action:
Either change the API call to createConnection() or change the connection factory type to QueueConnectionFactory.

BEA-169824
Failure occured on createTopicConnection. Unexpected return type.

Category:
JMSPool

Cause:
Probable cause is the JMS 1.1 ConnectionFactory with the JMS 1.0.2 createTopicConnection() API. Some JMS providers do not support backward compatibility.

Action:
Either change the API call to createConnection() or change the connection factory type to TopicConnectionFactory.

BEA-169825
Cannot create a wrapped JMSContext using a username and password when the res-auth element is set to Container.

Category:
JMSPool

Cause:
The application code is not using the Java EE APIs properly.

Action:
Either remove the username and password, or set the res-auth element to Application.

BEA-169826
The JMSContext pool named "{0}" has a configured connection factory JNDI name of "{1}". However, an object that is not a javax.jms.ConnectionFactory is bound to that JNDI name. The object bound to that JNDI name has type "{2}".

Category:
JMSPool

Cause:
An object other than a ConnectionFactory is bound to the configured JNDI name of the JMSContext pool.

Action:
Either change the JNDI name of the JMSContext pool property or change the JNDI name of the object that is currently bound into JNDI.

BEA-169827
The resource reference "{0}" of type JMS Connection Factory in application "{1}" does not specify a JNDI name. As of Java EE 7 and WebLogic version 12.2.1, such references return a "java:comp/DefaultJMSConnectionFactory" by default when no Connection Factory with a JNDI name that matches the resource name is found.

Category:
JMSPool

Cause:
See the error message from the JMS provider.

Action:
If the application intends to use a specific JMS Connection Factory, Oracle recommends (a) checking for a misspelling of the resource reference name either in the @Resource annotation or, if there is a deployment descriptor file, in the <resource-ref-name> of the deployment descriptor, and (b) if there is no misspelling, explicitly setting the desired JNDI name using a lookup or mappedName attribute in the descriptor or annotation.

BEA-169828
An invalid value ({0}) for session mode was specified.

Category:
JMSPool

Cause:
An invalid value of the sessionMode parameter was specified when creating a JMSContext. The only valid values are JMSContext.AUTO_ACKNOWLEDGE, JMSContext.CLIENT_ACKNOWLEDGE, JMSContext.DUPS_OK_ACKNOWLEDGE and JMSContext.SESSION_TRANSACTED

Action:
Change the code so that it passes in a valid session mode. See the JMS API for more information.

BEA-169829
JMS 2.0 method "{0}", called on the interface "{1}", is not implemented by this JMS Provider.

Category:
JMSPool

Cause:
JMS 2.0 method "{0}", called on the interface "{1}", is not implemented by this JMS Provider.

Action:
Either use a JMS 1.1 method instead or use a JMS provider that supports JMS 2.0.

BEA-169830
JMS Connection Factory unmapped resource reference mode : {0}

Category:
JMSPool

Cause:
This is an informational message.

Action:
No action is required.

BEA-169831
System property weblogic.jms.JMSConnectionFactoryUnmappedResRefMode has 2 legal values "{0}" and "{1}". The value "{2}" is invalid and will be ignored.

Category:
JMSPool

Cause:
There are two legal values for the weblogic.jms.JMSConnectionFactoryUnmappedResRefMode property.

Action:
No action is required.

BEA-169832
The JMS connection factory with JNDI name {0} is object-based-security enabled and is not supported by JMS pools.

Category:
JMSPool

Cause:
The JMS connection factory with JNDI name {0} is object-based-security enabled and is not supported by JMS pools.

Action:
Do not use object-based-security enabled JMS connection factory for JMS pools.

BEA-169833
A foreign server does not support referencing a Connection Factory that enables Object Based Security.

Category:
JMSPool

Cause:
A foreign server does not support referencing a Connection Factory that enables Object Based Security.

Action:
Configure the foreign server to reference a Connection Factory that does not enable Object Based Security.

BEA-170003
The DomainLogfile Handler is unable to open the domain logfile {0}. The domain logfile is disabled.

Category:
Log Management

Cause:
The filepath specified for the domain log is invalid or the server process cannot write to the domain log file.

Action:
Specify a valid filepath for the domain log file.

BEA-170011
The LogBroadcaster on this server failed to broadcast log messages to the Administration Server. The Administration Server may not be running. Message broadcasts to the Administration Server will be disabled.

Category:
Log Management

Cause:
The Managed Server may not be able to reach the Administration Server. One of the possible causes could be that the Administration Server is shut down.

Action:
To fix this problem, inspect the exception stack trace, and correct the problem. If the Administration Server is shut down, restart it to resume normal log broadcasting to the domain.

BEA-170019
The server log file {0} is opened. All server side log events will be written to this file.

Category:
Log Management

Cause:
This message is for informational purposes.

Action:
No action is needed.

BEA-170020
The server log file {0} could not be opened successfully.

Category:
Log Management

Cause:
The filepath configured for the server's log file is not valid.

Action:
Please specify a valid filepath for the server's log file.

BEA-170022
Log4j failed to initialize for {0}. The default JDK Logging implementation will be used.

Category:
Log Management

Cause:
The Log4j libraries may not be in the server CLASSPATH.

Action:
Take corrective action based on the stack trace details.

BEA-170023
The Server Logging is initialized with Java Logging API implementation.

Category:
Log Management

Cause:
This message is for informational purposes.

Action:
No action is needed.

BEA-170024
The Server Logging is initialized with Apache''s Log4j Logging API implementation.

Category:
Log Management

Cause:
This message is only for informational purposes.

Action:
No action is needed.

BEA-170025
Initialized Domain Logging. Domain log events will be written to {0}.

Category:
Log Management

Cause:
This message is for informational purposes.

Action:
No action is needed.

BEA-170026
The servlet context logger could not be initialized for servlet context {0} to write to its own log file.

Category:
Log Management

Cause:
There was an I/O error when opening the file for the servlet context log.

Action:
Ensure that the logging configuration for the web application is valid.

BEA-170027
The server has successfully established a connection with the Domain level Diagnostic Service.

Category:
Log Management

Cause:
The server has successfully established contact with the Domain Diagnostic Service.

Action:
No action is needed.

BEA-170028
The remote handler is not available, so the trap notification information can not be sent.

Category:
Log Management

Cause:
The Managed Server may not be able to reach the Administration Server. One of the possible causes could be that the Administration Server is shut down.

Action:
If the Administration Server is shut down, restart it to resume normal communication for the domain.

BEA-170029
The data gathering handler could not be initialized.

Category:
Log Management

Cause:
An error occurred while initializing the data gathering handler.

Action:
Review the nested exception details for the cause.

BEA-170030
There was an error initializing the global Log4j configuration.

Category:
Log Management

Cause:
The error could be due to incorrect configuration parameters in the log4j configuration file.

Action:
Review the nested exception details for the cause.

BEA-170031
The Server Logging bridge has initialized successfully.

Category:
Log Management

Cause:
This message is logged for informational purpose only.

Action:
No action is needed.

BEA-170032
The Server has detected ODL configuration for java.util.logging. The PlatformLoggerLevels attribute configuration on the LogMBean will be ignored.

Category:
Log Management

Cause:
This message is logged for informational purpose only.

Action:
Users should specify the java.util.logging Logger Level configuration with ODL.

BEA-170033
The Server logging bridge could not be registered.

Category:
Log Management

Cause:
See the stack trace for the exact cause of this error, it could be due to misconfiguration or incorrect CLASSPATH being set for the logging APIs.

Action:
Take appropriate action based on the error message.

BEA-170034
LogMonitoring Service counted {0} log messages in the last {1} seconds. This exceeds the throttle threshold value of {2}, certain repetitive messages will now be throttled.

Category:
Log Management

Cause:
This message is logged for informational purpose only.

Action:
No action is needed.

BEA-170035
LogMonitoring Service counted {0} log messages in the last {1} seconds which is below the threshold value of {2}. Log messages are not being throttled.

Category:
Log Management

Cause:
This message is logged for informational purpose only.

Action:
No action is needed.

BEA-170036
The Logging monitoring service timer has started to check for logged message counts every {0} seconds.

Category:
Log Management

Cause:
This message is logged for informational purpose only.

Action:
No action is needed.

BEA-170037
The log monitoring service timer has been stopped.

Category:
Log Management

Cause:
This message is logged for informational purpose only.

Action:
No action is needed.

BEA-170038
The log monitoring service is throttling messages with the following Message ID/LoggerName/Message signature and the total count of logged messages over the throttle period is: {0}

Category:
Log Management

Cause:
This message is logged for informational purpose only.

Action:
No action is needed.

BEA-170039
The log monitoring service encountered an error when it was trying to reopen the server log file.

Category:
Log Management

Cause:
The cause of the error is included in the error stack trace of the message.

Action:
Please take corrective action based on the error stack trace reported in the log message to resolve the issue.

BEA-170040
The log monitoring service detected missing Server log file and forced log rotation to reopen the server log file.

Category:
Log Management

Cause:
An external process or tool likely deleted the Server's current log file.

Action:
Please take corrective action to find the source of deletion and not delete the active log file being used by the Server.

BEA-171500
The embedded LDAP configuration file: {0} was not found, and the embedded LDAP server has not been started. To resolve the problem, ensure that weblogic.home is defined correctly (it should have a lib subdirectory that contains this file).

Category:
EmbeddedLDAP

Cause:
The embedded LDAP server cannot find the specified file. This file is installed as part of the installation process. Most likely, the default directory is not the server root directory and the lib subdirectory cannot be found.

Action:
Set the default directory to the server root directory, or use the weblogic.EmbeddedLDAPConfigDirectory system property to set the location of the embedded LDAP server configuration files.

BEA-171503
The listen address for the Administration Server is obtained from either the Server MBean, the ServerRuntime MBean, or the URL specified by the weblogic.management.server command line property. None of these returned a listen address.

Category:
EmbeddedLDAP

Cause:
The listen address was null.

Action:
Check if the listen address for the Administration Server is defined in either the Server MBean, the ServerRuntime MBean, or the URL specified by the weblogic.management.server command line property.

BEA-171507
The embedded LDAP replica file: {0} could not be written. The underlying exception was {1}.

Category:
EmbeddedLDAP

Cause:
An exception occurred when saving the replica properties to the replicas file.

Action:
Verify that the file {1} can be written. Read the exception text for more information in diagnosing the problem.

BEA-171512
When attempting to clean up after a failed embedded LDAP replica initialization, the file {0} could not be deleted. The {1} directory and all its files must be deleted manually.

Category:
EmbeddedLDAP

Cause:
It is not always possible to delete files that are open by a process.

Action:
Delete the {1} directory and all its files manually using the appropriate command for the operating system on which WebLogic Server runs.

BEA-171513
Could not schedule the trigger used for embedded LDAP timer activities. The underlying exception was {0}.

Category:
EmbeddedLDAP

Cause:
A TimeTrigger exception occurred when scheduling the trigger.

Action:
See the exception text in {0} for more information on diagnosing the problem.

BEA-171517
An error occurred while attempting to obtain exclusive access to the embedded LDAP data files directory: {0}. The exception that occurred is {1}.

Category:
EmbeddedLDAP

Cause:
An exclusive lock for the directory {0} could not be obtained because an exception occurred.

Action:
Investigate the associated exception to determine why the exclusive lock failed.

BEA-171518
The following exception has occurred:

Category:
EmbeddedLDAP

Cause:
An error condition has occurred.

Action:
Read the associated exception in the log. In general, a stack trace will help when debugging an existing problem.

BEA-171519
Could not obtain an exclusive lock to the embedded LDAP data files directory: {0} because another WebLogic Server instance is already using this directory. Ensure that the first WebLogic Server instance is completely shut down and restart the server.

Category:
EmbeddedLDAP

Cause:
An exclusive lock for the directory {0} could not be obtained because another WebLogic Server is already using this directory.

Action:
Ensure that the first WebLogic Server instance is shut down and try restarting the server.

BEA-171520
Could not obtain an exclusive lock for directory: {0}. Waiting for {1} seconds and then retrying in case the existing WebLogic Server instance is still shutting down.

Category:
EmbeddedLDAP

Cause:
An exclusive lock for the directory {0} could not be obtained because another WebLogic Server is already using this directory.

Action:
If the server eventually boots, ignore this warning as the lock was obtained. If the server fails to boot, ensure that the first WebLogic Server is shut down and try restarting the server.

BEA-171521
An error occurred while initializing the embedded LDAP server. The exception that occurred is {0}. This may indicate a problem with the data files for the embedded LDAP server. This Managed Server has a replica of the data contained on the master embedded LDAP server in the Administration Server. This replica has been marked invalid and will be refreshed on the next boot of the Managed Server. Try to reboot this server.

Category:
EmbeddedLDAP

Cause:
There may be a problem with either the embedded LDAP server configuration files or the data files.

Action:
Investigate the associated exception to determine why the exception occurred. Try to reboot the server and see if the refresh of the replica data files solves the problem.

BEA-171522
An error occurred while initializing the embedded LDAP server. The exception that occurred is {1}. This may indicate a problem with the data files for the embedded LDAP server. If the problem is with the data files, and it cannot be corrected, backups of previous versions of the data files exist in {0}.

Category:
EmbeddedLDAP

Cause:
There may be a problem with either the embedded LDAP server configuration files or the data files.

Action:
Investigate the associated exception to determine why the exception occurred. Try to reboot the server.

BEA-171523
Embedded LDAP server Credential unavailable: a credential value must be supplied for the embedded LDAP configuration.

Category:
EmbeddedLDAP

Cause:
The Credential attribute is invalid.

Action:
Set the Credential attribute for the embedded LDAP server configuration.

BEA-171524
Cannot determine the listen address for the Administration Server. The Administration Server URI {0}, obtained from either the Server MBean, the ServerRuntime MBean, or the URL specified by the weblogic.management.server command line property, has invalid syntax.

Category:
EmbeddedLDAP

Cause:
The Administration Server URI has invalid syntax.

Action:
Ensure that a valid listen address for the Administration Server is defined in either the Server MBean, the ServerRuntime MBean, or the URL specified by the weblogic.management.server command line property.

BEA-171525
Error loading initial replica file. Check the EmbeddedLDAP log for more details.

Category:
EmbeddedLDAP

Cause:
An error occurred during the loading of the initial replica file.

Action:
Check the EmbeddedLDAP log for more details.

BEA-171526
Error loading the initial replica file, attempting to reload.

Category:
EmbeddedLDAP

Cause:
An error occurred during the loading of the initial replica file.

Action:
No action is required. The initial replica file will be loaded again.

BEA-171527
Added all LDAP entries successfully for the initial replica.

Category:
EmbeddedLDAP

Cause:
An error occurred during the initial loading of the replica file.

Action:
No action is required. The reload of the initial replica file was successful.

BEA-171528
Could not mark replica as invalid.

Category:
EmbeddedLDAP

Cause:
The AdminServer was unable to connect to the managed server to mark it as invalid.

Action:
Reboot the managed server so its EmbeddedLDAP can be refreshed from the AdminServer.

BEA-171529
Unable to download the initial replica of security data from the AdminServer. Verify that clock skew has not occurred between the servers in the domain. The underlying exception was {0}

Category:
EmbeddedLDAP

Cause:
The managed server was unable to download the replica file due to an exception.

Action:
Verify that clock skew has not occurred between the servers in the domain. Read the exception text for more information in diagnosing the problem.

BEA-180000
Start parsing the configuration MBean information.

Category:
WTC

Cause:
All other initialization has completed, and this method is now ready to begin reading its own configuration information.

Action:
No action is required.

BEA-180001
WTC finished parsing the configuration MBean information.

Category:
WTC

Cause:
All WTC configuration MBeans were parsed without any problems.

Action:
No action is required.

BEA-180002
Invalid attributes exception occurred while trying to create subcontext: {0}

Category:
WTC

Cause:
An attempt was made to add an attribute set that has been specified incompletely or incorrectly.

Action:
Check for other log messages that give more information about the failure.

BEA-180003
Naming exception error: {0}

Category:
WTC

Cause:
The specified name could not be resolved.

Action:
Check for other log messages that give more information about the failure.

BEA-180004
Name already bound error: {0}

Category:
WTC

Cause:
The name used by the Tuxedo connection factory or Tuxedo CORBA connection factory already bonded to another object.

Action:
Do not use the same name as the Tuxedo or Tuxedo CORBA connection factory.

BEA-180005
Invalid attributes exception when binding connection factory: {0}

Category:
WTC

Cause:
An attempt was made to add an attribute set that has been specified incompletely or incorrectly.

Action:
Check for other log messages that give more information about the failure.

BEA-180006
Naming exception error: {0}

Category:
WTC

Cause:
The specified name could not be resolved.

Action:
Check for other log messages that give more information about the failure.

BEA-180007
Unable to register the resource with transaction manager: {0}.

Category:
WTC

Cause:
WebLogic Tuxedo Connector (WTC) was not running with the server transaction manager.

Action:
Contact My Oracle Support.

BEA-180008
A transaction identifier exists for a non-existent domain {0}.

Category:
WTC

Cause:
The remote Tuxedo domain involved in the transaction is no longer in the WebLogic Tuxedo Connector (WTC) configuration.

Action:
Manually correct the transaction. If the removal of the remote Tuxedo domain is intentional, temporarily add the remote Tuxedo domain back to the configuration and wait for the transaction to complete. Otherwise, add the Tuxedo domain back to the configuration.

BEA-180009
Could not complete the execution for the MBean named: {0}.

Category:
WTC

Cause:
The definition contains input information that is not consistent with the usage model.

Action:
Check the MBean definition to see if the individual attributes are consistent with the rest of the MBean definitions.

BEA-180010
Could not create a TDMLocalTDomain {0}.

Category:
WTC

Cause:
The AccessPoint attribute definition for the WTCLocalTuxDom MBean was invalid.

Action:
Check the AccessPoint attribute of the WTCLocalTuxDom MBean.

BEA-180011
Could not create a TDMRemoteTDomain {0}.

Category:
WTC

Cause:
The AccessPoint attribute definition for the WTCRemoteTuxDom MBean was invalid.

Action:
Check the AccessPoint attribute of the WTCRemoteTuxDom MBean.

BEA-180012
The LocalTDomain {0} is unknown.

Category:
WTC

Cause:
The LocalAccessPoint attribute for the WTCRemoteTuxDom MBean is not a valid name for a LocalTDomain.

Action:
Verify that the WTCRemoteTuxDom MBean definition has a valid name for the LocalAccessPoint attribute.

BEA-180013
The LocalTDomain {0} is unknown.

Category:
WTC

Cause:
The LocalAccessPoint attribute for the WTCExport MBean is not a valid name for a LocalTDomain.

Action:
Verify that the WTCExport MBean definition has a valid name for the LocalAccessPoint attribute.

BEA-180014
Could not create a TDMExport {0}.

Category:
WTC

Cause:
The ResourceName attribute definition for the WTCExport MBean is invalid or the LocalTDomain is not usable.

Action:
Check the ResourceName attribute of the WTCExport MBean.

BEA-180015
The LocalTDomain {0} is not known.

Category:
WTC

Cause:
The LocalAccessPoint attribute for the WTCImport MBean is not a valid name for a LocalTDomain.

Action:
Confirm that the WTCImport MBean definition has a valid name for the LocalAccessPoint Attribute.

BEA-180016
The RemoteTDomain {0} is unknown.

Category:
WTC

Cause:
The RemoteAccessPointList attribute for the WTCImport MBean does not contain a valid name for a RemoteTDomain.

Action:
Verify that the WTCImport MBean definition has valid names in a comma-separated list defined in the RemoteAccessPointList attribute.

BEA-180017
Could not create a TDMImport {0}.

Category:
WTC

Cause:
The ResourceName attribute definition for the WTCImport MBean is invalid. The LocalTDomain or the RemoteTDomains are not usable.

Action:
Check the ResourceName attribute of the WTCImport MBean.

BEA-180018
Missing {0} Password or PasswordIV information.

Category:
WTC

Cause:
The Password or PasswordIV attribute is not set.

Action:
Verify that the Password and PasswordIV attributes are valid.

BEA-180019
The LocalTDomain {0} is unknown.

Category:
WTC

Cause:
The LocalAccessPoint attribute for the WTCPassword MBean is not a valid name for a LocalTDomain.

Action:
Verify that the WTCPassword MBean definition has a valid name for the LocalAccessPoint attribute.

BEA-180020
The RemoteTDomain {0} is unknown.

Category:
WTC

Cause:
The RemoteAccessPoint attribute for the WTCPassword MBean is not a valid name for a RemoteTDomain.

Action:
Verify that the WTCPassword MBean definition has a valid name for the RemoteAccessPoint attribute.

BEA-180021
Could not create a TDMPasswd {0}.

Category:
WTC

Cause:
The LocalTDomain or the RemoteTDomain is not usable.

Action:
Check the LocalAccessPoint and RemoteAccessPoint attributes of the WTCPassword MBean.

BEA-180022
Could not set up the field table information for TDMResources: {0}.

Category:
WTC

Cause:
The fully qualified name for any field table may be incorrect or could not be found.

Action:
Check the FldTblClass definitions of the WTCResources MBean and verify that the fully qualified name is correct, that it is consistent with the current CLASSPATH usage, and that the system is able to access it.

BEA-180023
Commit of Xid failed with status {0}.

Category:
WTC

Cause:
The transaction became a heuristic hazard, or the resource manager encountered an error.

Action:
Correct the transaction manually if it became a heuristic hazard, or correct the resource manager problem.

BEA-180024
Unable to reply to unknown transaction with exception: {0}.

Category:
WTC

Cause:
The connection to the remote Tuxedo domain was already terminated or an IOException occurred while writing to the network.

Action:
If the TPException is TPEPROTO, try to reboot the remote Tuxedo domain. If the TPException is TPESYSTEM, check the network connection.

BEA-180025
Unknown field type requested {0}.

Category:
WTC

Cause:
TypedFML32 data is possibly being used instead of TypedFML.

Action:
Verify that the type of input data is correct.

BEA-180026
While trying to use FML data, this Ferror exception occurred: {0}

Category:
WTC

Cause:
The data was not created correctly.

Action:
Check the data that was passed into this method.

BEA-180027
While trying to use FML data, an Unknown exception occurred: {0}

Category:
WTC

Cause:
The data was not created correctly.

Action:
Check the data that was passed into this method.

BEA-180028
Unknown field type requested {0}.

Category:
WTC

Cause:
Possibly, TypedFML data is being used instead of TypedFML32.

Action:
Verify that the type of input data was correct.

BEA-180029
The Ferror exception: {0} occurred. Additional exception information found: {1}.

Category:
WTC

Cause:
The data was not created correctly.

Action:
Check the data that was passed into this method.

BEA-180030
While trying to use FML32 data, an Unknown exception occurred: {0}

Category:
WTC

Cause:
The data was not created correctly.

Action:
Check the data that was passed into this method.

BEA-180031
XML argument is null.

Category:
WTC

Cause:
The argument that was passed in was not initialized.

Action:
Check the XML argument that was passed in.

BEA-180032
The FldTbl[] input argument is null or an empty array.

Category:
WTC

Cause:
The argument that was passed in was not initialized.

Action:
Check the FldTbl[] argument that was passed in.

BEA-180033
TypedFML argument is null.

Category:
WTC

Cause:
The argument that was passed in was not initialized.

Action:
Check the TypedFML argument that was passed in.

BEA-180034
An error occurred while searching {0} for the document root element.

Category:
WTC

Cause:
The input XML string was not formatted correctly.

Action:
Check for other listed errors that should indicate what was unacceptable about the XML input.

BEA-180035
TypedFML32 argument is null.

Category:
WTC

Cause:
The argument that was passed in was not initialized.

Action:
Check the TypedFML32 argument that was passed in.

BEA-180036
XML input {0} caused the SAX parser exception {1}

Category:
WTC

Cause:
The Document Object Model (DOM) parser did not accept the XML string that it received.

Action:
Check the SAX exception information that was returned and the XML string that was entered.

BEA-180037
XML input {0} caused IOException {1}.

Category:
WTC

Cause:
The XML string was not convertible to an InputSource() class.

Action:
Check the IOException information that was returned and the XML string that was entered.

BEA-180038
XML input {0} caused an unknown exception {1}.

Category:
WTC

Cause:
The XML string was not able to be parsed.

Action:
Check the exception information that was returned and the XML string that was entered.

BEA-180039
The DOM parser returned a null value for input {0}.

Category:
WTC

Cause:
The input may not be a valid XML string.

Action:
Check the string that was passed to the parser.

BEA-180040
Could not obtain a top document element from input {0}.

Category:
WTC

Cause:
The XML input did not have any elements defined.

Action:
Verify that the input string has a proper definition for a root element.

BEA-180041
Could not obtain a tag name for the root element in XML input {0}.

Category:
WTC

Cause:
The XML input does not have a tag name for the root element.

Action:
Verify that the root element has a proper definition.

BEA-180042
Internal TypedFML data is null.

Category:
WTC

Cause:
The internal data that is using the XMLtoFML() API was not initialized.

Action:
Use XMLtoFML to initialize the internal data.

BEA-180043
XML element name is null.

Category:
WTC

Cause:
The XML element information was not properly defined.

Action:
Check the XML element definition.

BEA-180044
XML element value is null for the element name {0}.

Category:
WTC

Cause:
The XML element information was not properly defined.

Action:
Check the XML element definition.

BEA-180045
Internal TypedFML32 data is null.

Category:
WTC

Cause:
The internal data that was using the XMLtoFML32() API was not initialized.

Action:
Use XMLtoFML32 to initialize the internal data.

BEA-180047
The tBridge must have at least one redirect command.

Category:
WTC

Cause:
The tBridge was not configured properly.

Action:
At least one redirect command must be configured in the WTC_CONFIG for the tBridge section.

BEA-180048
The tBridge cannot find the TuxedoConnectionFactory.

Category:
WTC

Cause:
The WebLogic Tuxedo Connector (WTC) was not properly configured.

Action:
Review the WTC documentation and restart the WTC.

BEA-180049
The tBridge cannot locate the WLXT option for translation.

Category:
WTC

Cause:
The WLXT package might not be loaded or might be in the proper CLASSPATH.

Action:
Install the WLXT and properly configure the translator option.

BEA-180050
The tBridge internal FML-to-XML conversion failed.

Category:
WTC

Cause:
The syntax of the incoming message could not be understood.

Action:
Correct the message syntax and retry.

BEA-180052
Unable to cancel ON_STARTUP connection retry due to: {0}.

Category:
WTC

Cause:
The timer service object for the ON_STARTUP connection policy could not be deleted during connection termination.

Action:
Contact My Oracle Support.

BEA-180053
Failure occurred during the token creating token: {0}.

Category:
WTC

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-180054
Failure occurred while reading the received domain security token: {0}.

Category:
WTC

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-180055
Received an unexpected token type, error information({0}, {1}, {2}).

Category:
WTC

Cause:
The cause could be that WTC communicates with a newer version of the TDomain protocol or an unknown alien protocol, or a breach of security attempt was detected.

Action:
Verify who is trying to connect to this WTC and determine whether there is a security violation or a need to upgrade WTC to a newer version.

BEA-180056
atntd(1) crypto error: {0}

Category:
WTC

Cause:
There was not enough free memory space to continue.

Action:
Try to force garbage collection, and remove some services to reduce memory usage.

BEA-180057
Invalid return challenge

Category:
WTC

Cause:
This is caused by an incorrect configuration and mismatched password.

Action:
Correct the configuration and the password.

BEA-180058
atntd(3) I/O error: {0}

Category:
WTC

Cause:
This is an internal system error.

Action:
Contact My Oracle Support.

BEA-180059
atntd(2) crypto error: {0}

Category:
WTC

Cause:
There is not enough free memory space to continue.

Action:
Try to force garbage collection, and remove some services to reduce memory usage.

BEA-180063
Invalid handler address length: {0}.

Category:
WTC

Cause:
The client did not talk to a valid listener.

Action:
Check the listener address and correct the configuration.

BEA-180067
WSRPCRQ discriminator {0} is invalid.

Category:
WTC

Cause:
The client is not talking to a valid handler.

Action:
Check the configuration and correct the error.

BEA-180068
Invalid WSRPCRQ type {0}.

Category:
WTC

Cause:
The client is not talking to a valid handler.

Action:
Check the configuration and correct it.

BEA-180069
Unable to read {0}. The following exception occurred: {1}.

Category:
WTC

Cause:
A general I/O exception occurred.

Action:
Read the exception description to determine the actual cause and act accordingly.

BEA-180070
TypeFML32 received a pointer of unknown type {0}. Will replace with null.

Category:
WTC

Cause:
The application was incorrectly written with an unknown data type.

Action:
Correct the data type in the application.

BEA-180071
Invalid typed FML32 field {0}. Equals null.

Category:
WTC

Cause:
The embedded FML32 buffer was incorrectly constructed in the FML32 buffer.

Action:
Check the source of the embedded FML32 buffer, and correct the problem.

BEA-180074
The tpinit buffer was not received.

Category:
WTC

Cause:
The server is likely talking to an invalid handler.

Action:
Check the configuration and correct the problem.

BEA-180075
Invalid receive size {0}

Category:
WTC

Cause:
The remote tuxedo domain gateway is not valid.

Action:
Check the configuration of the remote Tuxedo domain and correct the error.

BEA-180076
Unable to format password. The following exception occurred: {0}.

Category:
WTC

Cause:
An I/O error occurred.

Action:
Check for system memory usage and see if force garbage collection is possible. If the problem persists, contact My Oracle Support.

BEA-180077
Unable to close the domain socket. The following exception occurred: {0}.

Category:
WTC

Cause:
An I/O error occurred while closing the socket.

Action:
Check the network and system environment. If the problem persists, contact My Oracle Support.

BEA-180078
Dropping OWS_AREPLY on ground.

Category:
WTC

Cause:
The ACALL request already timed out.

Action:
No action is required. This message is informational only.

BEA-180079
rsession.run read_tfmh failed.

Category:
WTC

Cause:
The received message header is not properly formatted or it failed to decompress the data.

Action:
Check the configuration of the remote Tuxedo domain and correct any problem in the configuration. Ensure that a supported version of the remote Tuxedo domain is being used. Also, check the network for possible network dropping of the packet. If the problem persists, contact My Oracle Support.

BEA-180080
rsession.run tmmsg.ws was not provided.

Category:
WTC

Cause:
There is no connection with a valid remote Tuxedo domain.

Action:
Check the remote Tuxedo domain configuration and correct the problem.

BEA-180081
Unexpected close on rsession socket. The following exception occurred: {0}

Category:
WTC

Cause:
An I/O error occurred while reading the message header from the input stream.

Action:
Check the system memory usage and force garbage collection. If the problem persists, contact My Oracle Support.

BEA-180082
Unable to close the WSH socket. The following exception occurred: {0}.

Category:
WTC

Cause:
An I/O error occurred.

Action:
Check the network and system configuration.

BEA-180083
An unknown TCM type was received: {0}.

Category:
WTC

Cause:
WebLogic Tuxedo Connector (WTC) is communicating with an unsupported Tuxedo version.

Action:
Check the configuration and correct the error.

BEA-180084
Unable to write TCM. The following exception occurred: {0}.

Category:
WTC

Cause:
An I/O error occurred.

Action:
Check the system memory usage and force garbage collection.

BEA-180085
Unable to send an unsolicited acknowledgment. The following exception occurred: {0}.

Category:
WTC

Cause:
An I/O error occurred.

Action:
Check the system memory usage.

BEA-180086
Accepted connection from the remote domain {0}.

Category:
WTC

Cause:
The connection request was received from a remote domain.

Action:
No action is required.

BEA-180087
Established a connection to a remote domain {0}.

Category:
WTC

Cause:
The connection request to a remote domain was initiated.

Action:
No action is required.

BEA-180088
Error occurred while building {0} message.

Category:
WTC

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-180089
Error occurred while decoding {0} message.

Category:
WTC

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-180090
Remote domain {0} rejected the connection request.

Category:
WTC

Cause:
An error exists in the configuration.

Action:
Check both sides of the configuration, including the password, to see whether a mismatch exists in the configuration.

BEA-180091
Rejected remote domain {0} connection request.

Category:
WTC

Cause:
An error exists in the configuration.

Action:
Check both sides of the configuration, including the password, to see whether a mismatch exists in the configuration.

BEA-180092
Failed security validation with remote domain {0}.

Category:
WTC

Cause:
An error exists in the configuraiton, resulting in unauthorized access.

Action:
Check both sides of the configuration, including the password, to see if a mismatch exists in the configuration.

BEA-180093
Naming exception occurred during the lookup of the administrator name: {0}.

Category:
WTC

Cause:
The specified name could not be resolved.

Action:
Contact My Oracle Support.

BEA-180094
The tBridge failed to initialize the JMS targetName queue.

Category:
WTC

Cause:
The JMS targetName queue does not exist or the JMS server was not running on the system.

Action:
Correct the JMS problem and restart the WebLogic Tuxedo Connector (WTC) tBridge.

BEA-180095
The tBridge could not initialize the JMS sourceName queue.

Category:
WTC

Cause:
The sourceName queue cannot exist in JMS or the JMS server was not started.

Action:
Correct the JMS problem and restart the WebLogic Tuxedo Connector (WTC) tBridge.

BEA-180096
The tBridge could not initialize the wlsErrorDestination JMS queue.

Category:
WTC

Cause:
The JMS wlsErrorDestination queue may not be properly configured in WebLogic Server.

Action:
Correct the JMS problem and restart the WebLogic Tuxedo Connector (WTC) tBridge.

BEA-180097
Due to a translation error, the tBridge has redirected the message to the wlsErrorDestination.

Category:
WTC

Cause:
A translation error was detected from XML-to-FML or from FML-to-XML.

Action:
Correct the message structure and resend the message.

BEA-180098
The tBridge failed to send the message to wlsErrorDestination.

Category:
WTC

Cause:
The JMS wlsErrorDestination could be full or paused.

Action:
Recover the message from the sourceName JMS queue and resend.

BEA-180099
The MinEncryptionBits is greater then the MaxEncryptionBits in {0} domain {1}.

Category:
WTC

Cause:
There is a configuration error.

Action:
Use the WebLogic Server Administration Console to modify the WebLogic Tuxedo Connector (WTC) configuration so that it will use the correct values for the MinEncryptionBits and MaxEncryptionBits.

BEA-180100
Configuration error: {0}

Category:
WTC

Cause:
There is a configuration error.

Action:
Use the WebLogic Server Administration Console to modify the WebLogic Tuxedo Connector (WTC) configuration so that it will use the correct values for the corresponding error.

BEA-180102
Duplicated local domain ID {0} found.

Category:
WTC

Cause:
Two local domains have the same ID.

Action:
Use the WebLogic Server Administration Console to modify the WebLogic Tuxedo Connector (WTC) configuration to use a unique ID for the local domain.

BEA-180103
There are two remote domains {0} with the same local domain {1}.

Category:
WTC

Cause:
Two remote domains have the same local domain.

Action:
Use the WebLogic Server Administration Console to modify the WebLogic Tuxedo Connector (WTC) configuration to remove the redundant entry or correct the configuration information.

BEA-180104
Unsupported JMS message type

Category:
WTC

Cause:
A JMS Stream or Mapped message type was sent to the tBridge.

Action:
Correct the JMS message type and resend.

BEA-180105
A message has been dropped.

Category:
WTC

Cause:
The most common cause of this failure is that an unrecognized buffer type has been received by the WTC gateway.

Action:
Modify the application to ensure that unknown buffer types are not sent to the WTC gateway.

BEA-180106
Unable to find a transaction manager. Transaction recovery will not continue.

Category:
WTC

Cause:
A transaction manager could not be found.

Action:
Contact My Oracle Support.

BEA-180107
While attempting to recover transactions, the recover method failed.

Category:
WTC

Cause:
The recover method on the WebLogic Server XA sesource generated an exception.

Action:
Contact My Oracle Support.

BEA-180108
WebLogic Server rollback had a failure: {0}.

Category:
WTC

Cause:
The rollback method on the WebLogic Server XA resource generated an exception.

Action:
Contact My Oracle Support.

BEA-180109
Internal FML to XML conversion failed.

Category:
WTC

Cause:
The FML buffer that was received from Tuxedo contained field buffer names that were not provided to WebLogic Tuxedo Connector (WTC). Therefore, the name translation failed.

Action:
Verify that the field tables have been properly transfered as described in the WTC documentation.

BEA-180110
Internal FML32-to-XML conversion failed.

Category:
WTC

Cause:
The FML32 buffer that was received from Tuxedo contained field buffer names that were not provided to the WebLogic Tuxedo Connector (WTC). Therefore, the name translation failed.

Action:
Verify that the field tables have been properly transferred as described in the WTC documentation.

BEA-180111
Internal FML to XML conversion failed.

Category:
WTC

Cause:
The FML buffer that was received from Tuxedo contained field buffer names that were not provided to the WebLogic Tuxedo Connector (WTC). Therefore, the name translation failed.

Action:
Verify that the field tables have been properly transferred as described in the WTC documentation.

BEA-180112
Internal FML32 to XML conversion failed.

Category:
WTC

Cause:
The FML32 buffer that was received from Tuxedo contained field buffer names that were not provided to the WebLogic Tuxedo Connector (WTC). Therefore, the name translation failed.

Action:
Verify the field tables have been properly transferred as described in the WTC documentation.

BEA-180115
The tBridge cannot parse the configuration MBeans: {0}.

Category:
WTC

Cause:
The MBeans for the tBridge contain invalid attributes.

Action:
Correct the attribute definitions for the tBridge MBeans.

BEA-180116
The specified field table type {0} is incorrect.

Category:
WTC

Cause:
The WTCStartup.getFldTbls() method was called with an invalid argument.

Action:
Verify that the Type argument for this is either fml16 or fml32.

BEA-180117
The encoding {0} is not supported. JVM default encoding is used.

Category:
WTC

Cause:
Specified encoding name is not supported.

Action:
Correct the encoding name and restart WebLogic Server.

BEA-180118
Failed to find TPUSR file: {0}.

Category:
WTC

Cause:
The specified file TPUSR file does not exist.

Action:
Correct the configuration by specifying the correct TPUSR file or create it before using the file.

BEA-180119
The specified filename is not a valid file: {0}.

Category:
WTC

Cause:
The WebLogic Tuxedo Connector (WTC) had the incorrect configuration.

Action:
Correct the WTC TPUSR file configuration.

BEA-180120
The file {0} is not readable.

Category:
WTC

Cause:
The user does not have the read permission to read the configured TPUSR file.

Action:
Change the permissions of the TPUSR file.

BEA-180121
Cannot find file {0}.

Category:
WTC

Cause:
The configured WebLogic Tuxedo Connector (WTC) TPUSR file does not exist.

Action:
Correct the WTC TPUSR file configuration or create the file.

BEA-180122
No permission to read the file {0}.

Category:
WTC

Cause:
The user does not have the read permission to read the configured TPUSR file.

Action:
Change the permissions of the TPUSR file.

BEA-180123
File I/O error for file {0}, reason: {1}.

Category:
WTC

Cause:
The file was corrupted or deleted.

Action:
Correct the file corruption or use a new TPUSR file.

BEA-180124
The specified number is not in a valid number format: {0}.

Category:
WTC

Cause:
The configured cache size was not in a valid number format.

Action:
Correct the configuration in the WebLogic Tuxedo Connector (WTC) TpUsrFile.

BEA-180132
Custom AppKey generator class {0} not found.

Category:
WTC

Cause:
The configured custom AppKey class full path name was incorrect.

Action:
Ensure that the configuration is correct and that the custom class exists.

BEA-180133
AppKey plug-in initialization failed. Reason: {0}

Category:
WTC

Cause:
The most likely reason is that the user database was not available or the initialization parameter was incorrect.

Action:
Ensure that the user database is available and that the configuration is correct.

BEA-180134
Create new AppKey class {0} instance failed.

Category:
WTC

Cause:
Either the class is not accessible, there is no permission to create a new instance of this class, or the class is not valid.

Action:
Ensure that the class is accessible with the correct permission. Also, the class must be based on the weblogic.wtc.jatmi.AppKey interface.

BEA-180136
The {0} attribute on the {1} MBean is undefined but required.

Category:
WTC

Cause:
The attribute value must be defined, but it was not defined.

Action:
Check that the MBean attribute is set correctly.

BEA-180137
The {0} attribute on the {1} MBean is set incorrectly.

Category:
WTC

Cause:
The attribute was defined improperly.

Action:
Check that the MBean attribute is set correctly.

BEA-180138
The {0} MBean appears to contain previously defined import service information.

Category:
WTC

Cause:
The attributes defined on this MBean have already been used to define and import a service.

Action:
Check that the Resourcename,RemoteAccessPointList, and LocalAccessPoint attributes are not all duplicated in another import MBean.

BEA-180139
A {0} type MBean is not defined, but it is required to be defined.

Category:
WTC

Cause:
An MBean was not defined, but it is required to be defined.

Action:
Check that the MBean type specified is defined in the configuration.

BEA-180141
Message header contains an invalid magic number, connection closed.

Category:
WTC

Cause:
Either an invalid TDOMAIN protocol data unit was received, or the remote domain gateway did not have network encoding enabled.

Action:
Ensure that the local access point is configured with the correct port number, and that the remote gateway does not have the same MTYPE configured for this TDOMAIN session.

BEA-180142
Local domain {0} in use and cannot be deleted.

Category:
WTC

Cause:
The local domain was in use by another resource.

Action:
Check for remote domains, imported or exported services, or passwords that use this local domain.

BEA-180143
Cannot find local domain {0}.

Category:
WTC

Cause:
The local domain could not be found.

Action:
Check the access point name.

BEA-180144
Duplicate remote domain {0}. Cannot add.

Category:
WTC

Cause:
The access point name was duplicated.

Action:
Check the access points and access point IDs for existing domains.

BEA-180145
Remote domain {0} in use. Cannot delete.

Category:
WTC

Cause:
The remote domain is referenced by another resource or has an active connection.

Action:
Shut down the connection to this remote domain. Check other resources that may reference this domain.

BEA-180146
Remote domain {0} cannot be found.

Category:
WTC

Cause:
The specified remote domain cannot be found.

Action:
Check the access point name for the remote domain.

BEA-180147
Cannot find imported service {0}.

Category:
WTC

Cause:
The specified imported service could not be found.

Action:
Check the name of the imported service.

BEA-180148
Cannot find exported service {0}.

Category:
WTC

Cause:
The specified exported service could not be found.

Action:
Check the name of the exported service.

BEA-180149
Cannot find password entry {0}.

Category:
WTC

Cause:
The specified password entry could not be found.

Action:
Check the local and remote access point names.

BEA-180150
Connection policy for {0} is INCOMING_ONLY.

Category:
WTC

Cause:
The connection policy specified INCOMING_ONLY, so an outbound connection could not be started.

Action:
Check the access point ID for the remote domain.

BEA-180151
Cannot modify resource {0} because it may be in use.

Category:
WTC

Cause:
There is an active connection that may use this resource.

Action:
Stop connections associated with this resource before attempting to delete the resource.

BEA-180152
Registration of notification listeners for the configured MBeans has failed.

Category:
WTC

Cause:
This is an internal system error.

Action:
Contact My Oracle Support.

BEA-180153
No valid host Internet address for WTC remote access point {0}.

Category:
WTC

Cause:
This is a configuration error.

Action:
Correct the WTC remote access point's network address list.

BEA-180154
No valid listening address configured for local access point {0}.

Category:
WTC

Cause:
This is an internal system error.

Action:
Contact My Oracle Support.

BEA-180155
No valid network address for TDomain session ({0}, {1}) to try to connect to.

Category:
WTC

Cause:
Either there is a configuration error or the remote access point was not available and cannot be accessed using the configured information.

Action:
Correct the configuration, or boot the remote access point.

BEA-180156
Failed to connect to remote access point(//{0}:{1}), try next address.

Category:
WTC

Cause:
Either a configuration error exists or the remote access point was not available at the address specified.

Action:
No action is required.

BEA-180157
Failed to connect to remote access point(//{0}:{1}), no more address to try.

Category:
WTC

Cause:
Either a configuration error exists or the remote access point was not available at the address specified.

Action:
Correct the configuration or make the remote access point available.

BEA-180158
No more valid network addresses for the local access point {0} to listen.

Category:
WTC

Cause:
There is a configuration error.

Action:
Correct the configuration.

BEA-180159
Failed to listen for local access point {0} on address (//{1}:{2}), try next address.

Category:
WTC

Cause:
Either a configuration error exists or this was intended.

Action:
No action is required.

BEA-180160
Failed to create listening endpoint for local access point {0} on address (//{1}:{2}), no more addresses to try.

Category:
WTC

Cause:
There is a configuration error.

Action:
Correct the configuration.

BEA-180161
Failed to find the imported service for QSpace {0}, so the tBridge has redirected the message to the wlsErrorDestination.

Category:
WTC

Cause:
The WebLogic Tuxedo Connector (WTC) import was incorrectly configured.

Action:
Correct the configuration.

BEA-180162
Cannot find imported service {0}, so the tBridge has redirected the message to the wlsErrorDestination.

Category:
WTC

Cause:
There is a configuration error.

Action:
Correct the configuration.

BEA-180163
The received Tuxedo reply uses the unsupported buffer type {0}, so the tBridge has redirected the message to the wlsErrorDestination.

Category:
WTC

Cause:
The Tuxedo server returned a reply with an unsupported buffer type.

Action:
Modify the Tuxedo server to return the reply with a WebLogic Tuxedo Connector (WTC) supported buffer type.

BEA-180164
Failed to send message to JMS, so the tBridge has redirected the message to the WLSErrorDestination.

Category:
WTC

Cause:
The JMS replyQ is configured incorrectly.

Action:
Correct the configuration of the JMS queue to be used for the tBridge reply queue.

BEA-180165
TDomain session ({0}, {1}) disconnected because no keep alive acknowledgement was received.

Category:
WTC

Cause:
A network outage may have occurred.

Action:
Check the network connection between the two gateways to determine if it is connected.

BEA-180166
The remote gateway does not support application level keep alive. This feature is disabled for the TDomain session ({0}, {1}).

Category:
WTC

Cause:
The remote gateway does not support this application level keep alive feature.

Action:
Update the remote gateway to a version of Tuxedo that supports the TDomain application level keep alive feature.

BEA-180167
The imported resource {0} uses a TDomain session ({1}, {2}) that does not exist.

Category:
WTC

Cause:
The imported resource was not configured properly.

Action:
Correct the configuration for the imported service.

BEA-180168
A connection cannot be established between local domain {0} and remote domain {1} due to a problem with the local or remote password used to authenticate the connections between these domains.

Category:
WTC

Cause:
The domain passwords were not configured properly.

Action:
Encrypt the correct local and remote passwords for the connection using the weblogic.wtc.gwt.genpasswd utility and use the results to configure a WTCPasswordMBean.

BEA-180169
XA.end() failed: {0}

Category:
WTC

Cause:
The transaction may have been marked as ROLLBACK_ONLY.

Action:
Inspect the application logic to determine the cause of the error.

BEA-180170
Unexpected exception while converting View {0} to XML: {1}

Category:
WTC

Cause:
Refer to the exception details.

Action:
Refer to the exception details.

BEA-180171
SSL null ciphers are not enabled and will be upgraded to the minimum 56 bits.

Category:
WTC

Cause:
The null cipher suites were disabled by SSL configuration.

Action:
This can be ignored because stronger encryption strength is allowed by WTC configuration and is also available by SSL. However, WTC configuration can be corrected to use only 56 bits and stronger cipher suites or SSL null ciphers can be enabled, if desired.

BEA-180172
SSL null ciphers are not enabled.

Category:
WTC

Cause:
The null cipher suites were disabled by SSL configuration.

Action:
Either the SSL null cipher suites must be explicitly enabled, or the WTC configuration must be updated to use stronger encryption cipher suites.

BEA-180173
Invalid private key for identity alias {0} from key store {1}, detected by {2}.

Category:
WTC

Cause:
An invalid key store or the private key alias configuration does not exist in the key store, or an incorrect private key store passphrase was configured.

Action:
Correct the key store or private key alias information in the configuration.

BEA-180174
Invalid private key store {0}, detected by {1}

Category:
WTC

Cause:
The private key store configured does not exist or is corrupted.

Action:
Correct the private key store configuration information.

BEA-180175
Invalid trust certificate store {0}, detected by {1}

Category:
WTC

Cause:
The private key store configured does not exist or is corrupted.

Action:
Correct the private key store configuration information.

BEA-180176
An error occurred while retrieving the trusted certificate from trust store {0}, detected by {1}.

Category:
WTC

Cause:
The configured trust certificate was corrupted or an incorrect passphrase was configured.

Action:
Correct the trust certificate store configuration information.

BEA-180177
An error occurred while retrieving trusted certificates from WebLogic Server, detected by {0}.

Category:
WTC

Cause:
The configured trust certificate was corrupted or an incorrect passphrase was configured.

Action:
Correct the trust certificate store configuration information.

BEA-180178
The requested encryption strength of 256 bits of local access point {0} is not supported by LLE. Downgrade to 128 bits.

Category:
WTC

Cause:
The configured encryption strength is not supported by LLE.

Action:
Either change the encryption strength to the LLE supported strength or use SSL for connection privacy. LLE supports 0, 40, 56, and 128 bits encryption strength. SSL supports 0, 56, 128, and 256 bits encryption strength.

BEA-180179
When enabling access point {0} to support SDP, the SSL support setting for this access point was ignored.

Category:
WTC

Cause:
When SDP is configured, SSL is not supported.

Action:
No action is required if SDP support is expected. Otherwise, update the configuration to disable SDP support.

BEA-180180
An error occurred while trying to open class com.oracle.net.Sdp when WTC support for SDP was enabled.

Category:
WTC

Cause:
The current JRE does not support SDP.

Action:
Use the JRockit version of the JRE provided with this release of WebLogic Server.

BEA-190000
Initializing Java EE Connector Service.

Category:
Connector

Cause:
The Java EE Connectoor Services is currently initializing.

Action:
No action required.

BEA-190001
Java EE Connector Service initialized successfully.

Category:
Connector

Cause:
The Java EE Connector Service has initialized successfully.

Action:
No action required.

BEA-190004
ConnectionFactory not found for jndiName {0}.

Category:
Connector

Cause:
This warning can occur upon viewing the JNDI tree for the Managed Server on the Administration Console. The other likely cause for this error is that an incorrect JNDI name was specified for the desired resource adapter or that the resource adapter is not deployed.

Action:
Ignore the warning if it occurs while viewing the JNDI tree of a Managed Server. Otherwise, check the deployed connectors in the Administration Console and verify the name that was used to access it.

BEA-190005
An error occurred while creating a connection factory for ManagedConnectionFactory with jndiName {0}.

Category:
Connector

Cause:
The cause is unknown. Consult the resource adapter vendor documentation.

Action:
Examine the exception in the log for more information about how to correct the problem. You may need to refer to the resource adapter vendor documentation to determine an appropriate course of action.

BEA-190008
An error occurred while {2} the connection instance {1} for {0} resource adapter. Exception is: {3}

Category:
Connector

Cause:
This error occurred as the result of an attempt to call cleanup() or destroy() on a resource adapter managed connection. The resource adapter can generate a ResourceException if the operation fails. It can also generate an IllegalStateException if, for example, an attempt was made to clean up a connection when a transaction was in progress. A ResourceAdapterInternalException may be generated if an error condition is detected in the resource adapter.

Action:
Examine the log for the exact type of exception that was generated. In the case of an IllegalStateException, report the error to My Oracle Support. In the case of a ResourceAdapterInternalException, report the error to the resource adapter vendor.

BEA-190009
No ConnectionRequestInfo was provided for Application Managed Security Context.

Category:
Connector

Cause:
No ConnectionRequestInfo was provided for Application Managed Security Context.

Action:
No action required.

BEA-190010
Unable to determine resource principal for the container-managed security context.

Category:
Connector

Cause:
Improper security principal map configuration for resource adapter.

Action:
Check the resource adapter configuration.

BEA-190012
Component using JNDIName: {0} has {1} managed security.

Category:
Connector

Cause:
The component with the indicated JNDI name has the indicated managed security type.

Action:
No action required.

BEA-190013
An error occurred while processing context: java:/comp/env/wls-connector-resref.

Category:
Connector

Cause:
This is an internal WebLogic Server error.

Action:
Report this error to My Oracle Support.

BEA-190019
< {0} > An error occurred when opening the log file {1} for the resource adapter.

Category:
Connector

Cause:
The log file is either a directory rather than a regular file, or it could not be opened for some other reason.

Action:
Check the log-filename configuration parameter in weblogic-ra.xml.

BEA-190020
< {0} > An error occurred while setting the log file to the resource adapter.

Category:
Connector

Cause:
An error occurred when WebLogic Server called the resource adapter's ManagedConnectionFactory.setLogWriter() method.

Action:
Contact your resource adapter supplier about the ManagedConnectionFactory.setLogWriter() method.

BEA-190023
< {0} > Error invoking the ManagedConnectionFactory "set" method for the configuration property "{1}". Reason: {2}

Category:
Connector

Cause:
The method required for setting the config-property could not be properly invoked.

Action:
Check the config-property of the ra.xml file in the resource adapter and ensure that the indicated property is specified correctly.

BEA-190024
< {0} > Error making initial connections for pool. Reason: {1}

Category:
Connector

Cause:
The backend system to which the resource adapter connects may be down, or the resource adapter may be misconfigured.

Action:
Check the availability of the backend system, then confirm the correct configuration of the resource adapter.

BEA-190032
< {0} > ResourceAllocationException generated by resource adapter on call to ManagedConnectionFactory.createManagedConnection(): "{1} "

Category:
Connector

Cause:
The cause should be evident from the exception. One likely cause is a misconfigured weblogic-ra.xml or ra.xml. The property(ies) specifying the connection information may not be correct.

Action:
Check the exception to determine the cause and attempt to remedy the indicated problem. You may need to consult the configuration for the resource adapter or the resource adapter documentation. You might also consult the resource adapter vendor support information or organization.

BEA-190033
< {0} > createManagedConnection returned a null ManagedConnection.

Category:
Connector

Cause:
This generally is a resource adapter error. A resource adapter should never return a null managed connection.

Action:
Check the exception to determine the cause and attempt to remedy the indicated problem. You may need to consult the configuration for the resource adapter or the resource adapter documentation, or consult the resource adapter vendor support information or organization

BEA-190049
The connector service failed to initialize. ServiceMBean initialization error: {0}

Category:
Connector

Cause:
This error should not occur under normal operations. Possible causes of this error could be low memory, file corruption, or machine instability.

Action:
Try rebooting the machine and restarting the server again. If the problem persists, note the error details and contact My Oracle Support.

BEA-190050
An error occurred in the connector service shutdown. Error: {0}

Category:
Connector

Cause:
The error occurred as a result of shutting down a connection pool or unregistering the ServiceMBean.

Action:
Report the error to My Oracle Support.

BEA-190051
An error occurred while shutting down the connection pool with pool name: {0}. Reason: {1}

Category:
Connector

Cause:
An error occurred while shutting down the connection pool. The error occurred while unregistering the ConnectionPoolRuntimeMBean. pool name:{0}. Reason: {1}

Action:
Report the error to My Oracle Support.

BEA-190052
An error occurred while creating a connection pool Runtime MBean with pool name: {0}. Reason: {1}

Category:
Connector

Cause:
An error occurred while creating a connection pool Runtime MBean. The error occurred while initializing the ConnectionPoolRuntimeMBean. pool name:{0}. Reason: {1}

Action:
Report the error to My Oracle Support.

BEA-190053
An error occurred while creating a resource for a connection pool {0}. Reason: {1}

Category:
Connector

Cause:
Error occurred while instantiating a ConnectionRuntimeMBean for the connection being created. Pool name: {0}. Reason: {1}

Action:
Report the error to My Oracle Support.

BEA-190054
An error occurred while destroying a resource for a connection pool {0}. Reason: {1}

Category:
Connector

Cause:
An error occurred while unregistering a ConnectionRuntimeMBean for the connection being destroyed. Pool name: {0}, Reason: {1}

Action:
Report the error to My Oracle Support.

BEA-190056
An error occurred while reserving a resource from a connection pool {0}. Reason: {1}

Category:
Connector

Cause:
An error occurred while registering an XAResource for the connection being reserved with the transaction manager. Pool name:{0}. Reason: {1}

Action:
Report the error to My Oracle Support.

BEA-190064
Access has been denied to {0}, Application: {1}, Module: {2}, EIS Type: {3}, while reserving a connection.

Category:
Connector

Cause:
The entitlement check did not pass for the connection request to the connection pool with name: {0}.

Action:
Check your entitlement configuration in the Administration Console.

BEA-190075
The resource adapter returned a null connection factory when createConnectionFactory was called for "{0}".

Category:
Connector

Cause:
The resource adapter is not functioning according to the specification.

Action:
Contact the resource adapter vendor.

BEA-190079
The descriptor element {0} has been replaced by {1}.

Category:
Connector

Cause:
A deprecated descriptor element has been detected.

Action:
Convert the old descriptor element to the replacement element.

BEA-190080
An inactive deprecated descriptor element {0} has been detected.

Category:
Connector

Cause:
An inactive deprecated descriptor element has been detected.

Action:
Refer to the connector documentation for more information.

BEA-190081
Testing resource adapter "{0}" for viability of connection proxies.

Category:
Connector

Cause:
The indicated resource adapter is currently being tested for viability connection proxies.

Action:
No action required.

BEA-190082
Proxy test passed. WebLogic Server will use connection proxies for resource adapter "{0}".

Category:
Connector

Cause:
The proxy test passed for the incidated resource adapter.

Action:
No action required.

BEA-190084
Unable to complete connection proxy test for "{0}" due to the following exception. WebLogic Server will attempt to use connection proxies for resource adapter "{0}" as usual.

Category:
Connector

Cause:
WebLogic Server attempted to pose as an application component to determine whether a generated proxy class is compatible with a resource adapter (to support late transaction enlistment and leak and idle detection of connections). The connection proxy test failed.

Action:
No action is required.

BEA-190085
The linkref RAR {0} has been marked for late deployment since its base has not been deployed.

Category:
Connector

Cause:
The base RAR that the linkref points to has not been deployed yet.

Action:
Do not use the linkref until its base has been deployed.

BEA-190088
Trying to deploy a connector with a JNDI name that already exists {0}.

Category:
Connector

Cause:
Trying to deploy a connector with a JNDI name that already exists {0}.

Action:
Use a unique JNDI name while deploying the connector.

BEA-190089
Unexpected error occurred while processing a resource adapter JAR file.

Category:
Connector

Cause:
The cause is unknown.

Action:
Examine the stack trace for the cause and action.

BEA-190090
Call to implementation of ManagedConnection.getLocalTransaction in resource adapter with jndiName = {1} failed: {0}

Category:
Connector

Cause:
Refer to the error message for more information.

Action:
See the error message for more information. If it is still unclear, contact the resource adapter vendor or My Oracle Support.

BEA-190091
Call to implementation of ManagedConnection.getXAResource in resource adapter with jndiName = {1} failed: {0}

Category:
Connector

Cause:
Refer to the error message for more information.

Action:
Refer to the error message for more information. If still unclear, contact the resource adapter vendor or My Oracle Support.

BEA-190092
An error occurred while reserving a resource from a connection pool {0}. Reason: {1}

Category:
Connector

Cause:
An error occurred while registering a non-XAResource for the connection being reserved with the transaction manager. pool name:{0}. Reason: {1}

Action:
Report this error to My Oracle Support.

BEA-190097
Unable to complete the connection proxy test for "{0}" due to an exception. WebLogic Server will attempt to use connection proxies for resource adapter "{0}" as usual. Exception: {1}

Category:
Connector

Cause:
WebLogic Server attempted to pose as an application component to determine whether a generated proxy class is compatible with a resource adapter (to support late transaction enlistment and leak and idle detection of connections). The connection proxy test failed.

Action:
No action is required.

BEA-190098
Trying to release a resource that has already been released for {0}.

Category:
Connector

Cause:
Trying to release a resource that has already been released for {0}. It is possible that the connection was already released due to an error that occurred with the connection.

Action:
No action is required.

BEA-190099
Attempting to close a connection that has already been closed for {0}.

Category:
Connector

Cause:
An attempt was made to close a connection that has already been closed for {0}.

Action:
No action is required.

BEA-190100
A close() method was not found on the connection handle while testing for the viability for connection proxies : {0}

Category:
Connector

Cause:
A close() method was not found on the connection handle while testing for the viability for connection proxies : {0}. As per the 1.0 specification, a close() method is required on the connection handle.

Action:
Implement a close() method for the connection handle.

BEA-190101
Linkrefs are deprecated for 1.0 resource adapters: {0}

Category:
Connector

Cause:
Linkrefs are deprecated for 1.0 resource adapters.

Action:
No action is required.

BEA-190102
Failed to unregister the Diagnostic Image for the Connector Service.

Category:
Connector

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-190103
Failed to register the Diagnostic Image for the Connector Service.

Category:
Connector

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-190104
While configuring an object of type: {0} of Resource Adapter {1}, the following errors/omissions were found: {2}

Category:
Connector

Cause:
Properties have been specified in a resource adapter deployment descriptor which are inconsistent with those defined by the resource adapter code. There may be properties specified in the descriptor that do no exist in the object or are of the wrong type.

Action:
Check that the specified properties are spelled properly. Check with the resource adapter documentation or the vendor to determine whether or not these warnings can be ignored.

BEA-190105
Failed to initialize the AnonymousSubject.

Category:
Connector

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-190106
Failed to find the RuntimeMBean for the module: {0}

Category:
Connector

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-190107
Failed to unregister the RuntimeMBean for the module: {0}

Category:
Connector

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-190108
Failed to initialize the Jndi Subcontexts for the adapter: appId = {0}, {1}

Category:
Connector

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-190109
Extracting file {0} to {1}.

Category:
Connector

Cause:
The indicated file is being extracted to the indicated native Lib directory.

Action:
No action required.

BEA-190110
Resource adapter is calling BootstrapContext.createTimer() and allocating a Timer Thread that is not managed by WebLogic Server. This may adversely impact the performance or operation of WebLogic Server.

Category:
Connector

Cause:
A resource adapter is calling BootstrapContext.createTimer() and allocating a Timer Thread that is not managed by WebLogic Server.

Action:
Contact the resource adapter vendor and notify them of this warning condition.

BEA-190111
InvalidDyeException was generated: Module Name = {0}, {1}.

Category:
Connector

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-190112
Failed to register the XAResource to be used for recovery: {0}

Category:
Connector

Cause:
See the error description in the message body.

Action:
See the stack trace and report the error to My Oracle Support.

BEA-190113
Failed to Unregister the XAResource used for recovery: {0}

Category:
Connector

Cause:
See the error description in the message body.

Action:
See the stack trace and report the error to My Oracle Support.

BEA-190114
Failed to apply dynamic pool changes: {0}

Category:
Connector

Cause:
See the error description in the message body.

Action:
See the error description in the message body.

BEA-190115
The ManagedConnectionFactory class does not implement the ResourceAdapterAssociation interface: {0}

Category:
Connector

Cause:
See the error in the message body for information.

Action:
Please contact the resource adapter vendor and notify them of this error condition.

BEA-190116
An invalid event was triggered on the XAResource used for recovery: {0}

Category:
Connector

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-190117
Invocation of ManagedConnection.cleanup() failed: {0}

Category:
Connector

Cause:
See the error in the message body for information.

Action:
Examine the stack trace and error message for more information.

BEA-190118
ConnectionErrorOccurred event was triggered: {0}

Category:
Connector

Cause:
The adapter has indicated an error occurred on the exception.

Action:
Examine the stack trace and error message for more information.

BEA-190119
Invocation of ManagedConnection.destroy() failed: {0}

Category:
Connector

Cause:
The implementation of the resource adapter's cleanup() method threw an exception.

Action:
Examine the stack trace and error message for more information.

BEA-190120
Invocation of ManagedConnection.getXAResource() returned null.

Category:
Connector

Cause:
The implementation of the resource adapter's getXAResource() returned null.

Action:
Please contact the resource adapter vendor to determine why getXAResource() returned null.

BEA-190121
Failed to dissociate the Connection Handles from a ManagedConnection: Adapter JndiName = {0}, {1}

Category:
Connector

Cause:
See the stack trace for details about the cause of this error.

Action:
Take appropriate action based on the information in the stack trace.

BEA-190122
The resource adapter passed a null ManagedConnection into WebLogic Server''s implementation of ConnectionManager.lazyEnlist().

Category:
Connector

Cause:
The resource adapter's implementation passed a null ManagedConnection into the lazyEnlist() method.

Action:
Please notify the resource adapter's vendor about this error.

BEA-190123
Outbound adapter for jndiName = {0}, is using sharing scope = {1}.

Category:
Connector

Cause:
The outbound adapter with the indicated JNDI name is using the indicated sharing scope.

Action:
No action required.

BEA-190124
Failed to deploy LinkRef Adapter, moduleName = {0}, baseRA = {1}, Exception: {2}

Category:
Connector

Cause:
Refer to the message body and exception message for more information.

Action:
Refer to the message body and exception message for more information.

BEA-190125
An internal consistency check failed, assertion failed: {0}

Category:
Connector

Cause:
An internal consistency check failed, indicating a software defect.

Action:
Check for other log messages that give more information about the failure.

BEA-190126
anonymous

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190127
CloseCount

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190128
CreateCount

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190129
FreePoolSize

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190130
PoolSize

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190131
WaitingThreadCount

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190133
Number of times create was called on the connection pool

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190134
Number of connections in the pool that are free for use

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190135
Size of the connection pool

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190136
Number of threads in the waiting state

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190137
Never

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190138
<Unavailable>

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190139
Running

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190140
Suspended

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190141
New

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190142
Initialized

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190143
Prepared

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190144
Activated

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190145
Unknown

Category:
Connector

Cause:
This message is used only for localization (internationalization) purposes.

Action:
No action is required.

BEA-190146
An error occurred while setting the log file to the resource adapter"s ManagedConnectionFactory: {0}. The exception was "{1}" with cause "{2}".

Category:
Connector

Cause:
An error occurred when WebLogic Server called the resource adapter's ManagedConnectionFactory.setLogWriter() method.

Action:
Examine the message and cause, or contact the resource adapter provider, or both.

BEA-190147
Profiling Record for Pool: PoolName = "{0}", Type = "{1}", Timestamp = "{2}", Properties : {3}

Category:
Connector

Cause:
This message is informational. The Harvester logged this Profiling Record for debug purposes.

Action:
No action is required.

BEA-190148
The attempt to set the property "{1}" of type "{2}" of object "{0}" to value "{3}" failed with a PropertyVetoException generated by the resource adapter. The veto message was "{4}".

Category:
Connector

Cause:
See the veto message for more information.

Action:
See the veto message for more information. Contact the resource adapter provider if more assistance is needed.

BEA-190149
No JNDI Name has been specified for the resource adapter in module {0} of application {1}. Since this is an inbound resource adapter, <jndi-name> must also be specified in weblogic-ra.xml for endpoint activation by a message endpoint MDB to work.

Category:
Connector

Cause:
There is a missing <jndi-name> element in weblogic-ra.xml.

Action:
Specify the <jndi-name> in weblogic-ra.xml that corresponds to the JNDI name expected by the MDB that is using this inbound resource adapter.

BEA-190150
The process of creating the Connector Diagnostic Image has been timed out by the Diagnostic Framework. The resulting image may be incomplete.

Category:
Connector

Cause:
The process of creating the Connector Diagnostic Image has been timed out by the Diagnostic Framework.

Action:
Please investigate the contents of the log and Diagnostic Images for more information.

BEA-190151
Parsing error, buildOutboundResourceAdapter() error in parsing ra.xml. While looking for connectionfactory-interface, failed to find: "{0}"

Category:
Connector

Cause:
There is an error in the XML configuration for this adapter.

Action:
Please contact the vendor to obtain a resource adapter with a valid configuration.

BEA-190152
Failed to create a new ConnectorInboundRuntimeMBeanImpl for "{0}", {1}

Category:
Connector

Cause:
See the error in the logged message for more information.

Action:
See the error in the logged message for more information.

BEA-190153
Failed to close the logging stream for pool: "{0}", {1}

Category:
Connector

Cause:
See the error in the logged message for more information.

Action:
See the error in the logged message for more information.

BEA-190154
Failed to create the logging stream for pool: "{0}", {1}

Category:
Connector

Cause:
See the error in the logged message for more information.

Action:
See the error in the logged message for more information.

BEA-190155
Compliance checking and validation of the resource adapter {0} resulted in the following warnings: {1}

Category:
Connector

Cause:
The specified resource adapter failed to pass compliance and validity checking as indicated by the listed warnings and errors.

Action:
Correct the ra.xml, weblogic-ra.xml or the resource adapter archive.

BEA-190156
There were no compliance or validation errors found in the resource adapter {0}.

Category:
Connector

Cause:
No compliance or validation errors were found in the indicated resource adapter.

Action:
No action required.

BEA-190157
There were {1} critical compliance or validation error(s), {2} non-critical compliance or validation error(s), and {3} warning(s) found in the resource adapter {0}.

Category:
Connector

Cause:
This message is logged to incidate the number of errors and warnings that were found for the indicated resource adapter.

Action:
No action required.

BEA-190158
This is a link ref resource adapter for {0}. No validation can be done at this time.

Category:
Connector

Cause:
Since there is no ra.xml in this resource adapter, validation of the adapter cannot be performed until it and the base adapter are deployed.

Action:
No action is required.

BEA-190159
Connection Pool {0} has been reset.

Category:
Connector

Cause:
The indicated connection pool was reset.

Action:
No action required.

BEA-190160
Connection pool {0} is in use and cannot be reset. Try forceReset instead.

Category:
Connector

Cause:
Since there are connections reservered from connection pool {0}, reset of the pool cannot be performed.

Action:
Try forceReset instead.

BEA-190161
Failed to extract adapter {0} to server temporary directory due to exception {1}.

Category:
Connector

Cause:
Extraction of the adapter {0} to server temporary directory failed due to the exception.

Action:
Check the permissions on the server temporary directory or check the exception.

BEA-190162
Failed to create server temporary directory {1} while extracting adapter {0}.

Category:
Connector

Cause:
Creation of the server temporary directory {1} failed while extracting the adapter {0}.

Action:
Check the permissions on the server temporary directory.

BEA-199000
Only positive values are allowed for initial-capacity unless initial and max capacity are equal.

Category:
Connector

Cause:
Refer to the message body and exception for more information.

Action:
Refer to the message body and exception for more information.

BEA-199001
Zero value for max-capacity is allowed only for link-ref adapters.

Category:
Connector

Cause:
The max-capacity is zero.

Action:
Check the max-capacity and update it.

BEA-199002
Negative values are not allowed for max-capacity.

Category:
Connector

Cause:
The max-capacity is negative.

Action:
Check the max-capacity and update it.

BEA-199003
max-capacity should be greater than or equal to initial-capacity. {0}

Category:
Connector

Cause:
The max-capacity is less than initial-capacity.

Action:
Check the max-capacity and update it.

BEA-199004
Only positive values are allowed for capacity-increment.

Category:
Connector

Cause:
The capacity-increment is zero or negative.

Action:
Check the capacity-increment and update it.

BEA-199005
capacity-increment should be less than or equal to (max_capacity-initial_capacity). {0}

Category:
Connector

Cause:
The capacity-increment is greater than max_capacity-initial_capacity.

Action:
Check the capacity-increment and update it.

BEA-199006
Only positive values are allowed for shrink-frequency-seconds.

Category:
Connector

Cause:
The shrink-frequency-seconds is zero or negative.

Action:
Check the shrink-frequency-seconds.

BEA-199007
Only values greater than or equal to 0 are allowed for inactive-connection-timeout-seconds.

Category:
Connector

Cause:
The value of inactive-connection-timeout-seconds must be positive.

Action:
Please check the inactive-connection-timeout-seconds.

BEA-199010
No ra.xml or weblogic-ra.xml has been specified. The RAR is null and there is no alternate descriptor.

Category:
Connector

Cause:
The deployment descriptor for this adapter cannot be found.

Action:
Define the deployment descriptor in ra.xml or weblogic-ra.xml or an annotation.

BEA-199011
No ra.xml or weblogic-ra.xml has been specified.

Category:
Connector

Cause:
The deployment descriptor for this adapter could not be found.

Action:
Define the deployment descriptor in ra.xml or weblogic-ra.xml.

BEA-199012
Unable to find the schema.

Category:
Connector

Cause:
The schema could not be found.

Action:
Check the location of the schema for the XML file.

BEA-199013
Application {0} does not have any components in it.

Category:
Connector

Cause:
The application does not contain any components.

Action:
Add components in the application and define them in the deployment descriptor.

BEA-199014
Application {0} is a RAR file, but it contains more than 1 component.

Category:
Connector

Cause:
The application contains multiple adapter components.

Action:
Check the deployment descriptor or the annotation.

BEA-199015
Error occurred while trying to rollback the module: {0}

Category:
Connector

Cause:
The module cannot be rolled back. See the reported error for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199016
Unable to create runtime MBean for connector: Module "{0}", {1}

Category:
Connector

Cause:
The runtime MBean cannot be created. See the reported error for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199017
Error closing virtual JAR file for {0}, {1}

Category:
Connector

Cause:
The virtual JAR file cannot be closed. See the reported error for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199018
Error creating virtual JAR file for {0}, {1}

Category:
Connector

Cause:
The virtual JAR file cannot be created. See the reported error for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199019
Failed to initialize the connector-specific JNDI sub-contexts for the application, {0}, {1}

Category:
Connector

Cause:
The connector-specific JNDI sub-contexts cannot be initialized. See the reported error for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199020
Failed to prepare changes for dynamic update, {0}, {1}

Category:
Connector

Cause:
Changes for dynamic update cannot be prepared. See the reported error for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199021
JNDI name is null or empty.

Category:
Connector

Cause:
The JNDI name must contain characters that are not spaces.

Action:
Check the JNDI name.

BEA-199022
Unable to get InitialContext while attempting to verify JNDI name of a resource adapter object.

Category:
Connector

Cause:
Failed to create the InitialContext.

Action:
Check the environment properties of the InitialContext.

BEA-199023
ResourceLink is null or empty.

Category:
Connector

Cause:
ResourceLink is null or empty.

Action:
Check the ResourceLink.

BEA-199024
Unable to get InitialContext while attempting to verify resource link of resource adapter.

Category:
Connector

Cause:
The InitialContext cannot be created.

Action:
Check the environment properties of the InitialContext.

BEA-199028
Resource Adapter with JNDIName: {0} already deployed.

Category:
Connector

Cause:
Multiple apdaters are deployed with the same JNDI name.

Action:
Change the adapter's JNDI name in deployment descriptor.

BEA-199029
Bind operation failed: {0}, {1}

Category:
Connector

Cause:
The JNDI name cannot be bound. See the reported error for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199031
Failed to unbind the ConnectionFactory, {0}, {1}

Category:
Connector

Cause:
The ConnectionFactory cannot be unbound. See the reported error for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199032
Unable to getInitialContext() during unbindConnectionFactory, {0}

Category:
Connector

Cause:
The getInitialContext() method cannot be called. See the reported exception for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199036
ResourceLink: {0} already bound into application-scoped JNDI tree.

Category:
Connector

Cause:
The ResourceLink has been bound into the JNDI tree.

Action:
Change the JNDI name of ResourceLink.

BEA-199037
Unable to bind to the app-scoped jndi tree: {0}#{1} : {2}

Category:
Connector

Cause:
The ResourceLink cannot be bound. See the reported error for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199038
NamingException while trying to unbind references during unbindAdminObject of resource adapter, {0}

Category:
Connector

Cause:
AdminObjects cannot be unbound. See the reported error for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199039
Unable to get the connection factory for {0}. Verify that the resource adapter has been deployed.

Category:
Connector

Cause:
The connection factory cannot be found.

Action:
Verify that the resource adapter has been deployed.

BEA-199041
An exception occurred while calling newInstance in the Resource Adapter, classname = {0}, Exception = {1}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199042
An exception occurred while trying to create the Connector Diagnostic Image, Exception = {0}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199043
Trying to prepare a resource adapter that has not been initialized.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199044
Trying to activate a resource adapter that has not been prepared. Current state : {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199045
Trying to rollback an RA that is in the ACTIVATED state

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199046
Unable to create the native lib directory.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199047
Bad resource adapter class specification for class "{0}": {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199048
Trying to version a resource adapter that is not versionable.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199049
Unable to populate the Work Manager during resource adapter initialization.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199050
Caught exception while starting the resource adapter : {0}, {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199051
Caught exception while creating the BootstrapContext : {0}, {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199052
Unable to version the resource adapter.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199053
Unable to set up the work runtimer.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199054
Unable to introspect the object that was passed in. {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199055
Unable to get the setter method for the key: {0}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199056
Unable to invoke the setter method for the key: {0}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199065
An invalid type {0} has been specified for a key.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199066
For property "{0}", the type and value do not match. Type = {1}, Value = {2}, Exception: {3}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action accordingly.

BEA-199067
LoginException while trying to establish security identity for user "{0}" in weblogic-ra.xml element {2}: {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199068
No deployed ResourceAdapter with adapter JNDI name = "{0}" was found.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199071
Unable to initialize ActivationSpec {0}. Cause unknown.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199072
Failed to instantiate class {0}, {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199073
{0} passed {1} of "{2}".

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199074
Required Configuration Properties Missing in ActivationSpec: {0}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199075
Located a resource adapter with JNDI name = "{0}", but that adapter is not yet fully deployed and active.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199076
Could not locate a resource adapter with JNDI name = "{0}".

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199077
The resource adapter with JNDI name = "{0}" does not have a <messagelistener> element with a <messagelistener-type> of "{1}".

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199089
The resource adapter does not have a <inbound-resourceadapter> element in ra.xml.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199090
The resource adapter does not have a <messageadapter> element in ra.xml.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199091
The resource adapter does not have any <messagelistener> elements in ra.xml.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199092
Internal error occurred, Assertion Failed: {0}

Category:
Connector

Cause:
An internal consistency check failed indicating a software defect.

Action:
Please note the circumstances of the error as well as any related log messages and contact My Oracle Support.

BEA-199093
setDyeBits failed because diagnostic contexts are not enabled.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199094
Invalid dye value specified, {0}. Value must be between 0 and 15 in order to fit within a 4-bit space.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199095
getDyeBits failed, moduleName = {0}: {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199096
setDyeBits failed: Failed to obtain Diagnostic Context. ModuleName = {0}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199097
getDyeBits failed because Diagnostic Contexts are not enabled.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199098
This connection does not meet the criteria for manual deletion.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199099
Failed to setup the Resource Adapter Connection for enlistment in the transaction, Pool = "{0}", {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199100
Resource Adapter threw Non-ResourceException from its implementation of ManagedConnection.getLocalTransaction(), Pool = "{0}", {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199101
Resource Adapter returned null from its implementation of ManagedConnection.getLocalTransaction(), Pool = "{0}".

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199102
Unable to register NonXAResource, {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199103
Commit Failed: {0}, Stack Trace: {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199104
Rollback Failed: {0}, Stack Trace: {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199105
Resource Adapter returned null from ManagedConnection.getXAResource() while trying to obtain XAResource for recovery.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199106
Resource Adapter threw non-ResourceException in call to ManagedConnection.getXAResource(): {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199107
Resource Adapter returned null from ManagedConnectionFactory.createManagedConnection() while trying to create ManagedConnection for recovery.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199108
Failed to initialize ManagedConnection for recovery: {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199109
Connector Internal Error: Illegal type found during enlistResource.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199110
Connector Internal Error: Invalid type found in registerResource: {0}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199111
Attempt to start an XA Transaction inside a Resource Adapter"s Local Transaction is illegal.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199112
Failed to create managed connection: {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199113
Failed to setup the ManagedConnection with WLS after successfully getting it from a call to the Resource Adapter"s ManagedConnectionFactory.createManagedConnection method.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199114
Internal WLS Connector Error: Object Id is null.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Please contact My Oracle Support.

BEA-199116
Resource Adapter Error: getConnection method returned null from the adapter"s ManagedConnection implementation in class "{0}".

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199117
The resource adaptor has returned the same connection handle that was returned on a prior call to getConnection(). A new connection handle must be returned with every call to getConnection() as per the JCA specification.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199118
While testing connection, the adapter''s implementation of getInvalidConnections() threw ResourceException: {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199119
While testing connection, the adapter''s implementation of getInvalidConnections() threw non-ResourceException: {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199120
Connections should not be tested for a ManagedConnectionFactory that does not implement ValidatingManagedConnectionFactory.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199121
The ResourceAdapter with pool = "{0}" passed a null value to the Application Server"s implementation of the lazyEnlist method for the ConnectionManager class.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199122
Access to resource adapter, with pool = "{0}", has been denied.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199123
Unable to get a connection for pool = "{0}", {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199124
Pool "{0}" is disabled, cannot allocate resources to applications.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199125
The resource adapter"s implementation of ManagedConnectionFactory returned null from the createConnectionFactory() method.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199126
Stack trace at connection create:

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199127
Local Transaction not supported for this Resource Adapter.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199128
The connection handle has not been set for the connection closed event as per the JCA specification.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199129
Error preparing the pool with key : "{0}", {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199130
Unable to resume the pool, {0}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199131
Unable to bind to the jndi tree : "{0}", {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199132
Key = {0}, Message = {1}, Exception = {2}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199133
Unable to shut down the pool : Key = "{0}", Message = {1}, Exception = {2}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199134
Attempting to create a connection factory with a JNDI name that already exists: "{0}".

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199135
Attempting to create a connection factory with a resource link that already exists: "{0}".

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199136
There was a problem verifying the JNDI name of the outbound connection: {0}, {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199137
The ManagedConnectionFactory class implementation "{0}" does not implement the ResourceAdapterAssociation interface and does not implement setResourceAdapter() and/or getResourceAdapter().

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199138
Unable to set the ResourceAdapter class for the mcf "{0}", {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199139
Unexpected exception thrown by resource adapter"s ManagedConnectionFactory implementation "{0}", {1}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Take appropriate action based on the cause reported in the logs.

BEA-199140
Could not find the managed connection factory class "{0}", {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199141
Failed to instantiate the resource adapter"s implementation of the ManagedConnectionFactory class "{0}," {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199142
Unable to access the Resource Adapter" implementation of the ManagedConnectionFactoryClass "{0}", {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199143
Internal WebLogic Server Connector Error: Failed to get the connection pool for jndiName: "{0}".

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Please contact My Oracle Support.

BEA-199144
A resource adapter may only be accessed from within the same application from which it was deployed.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199145
Operation is not supported, {0}, {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199146
If only a weblogic-ra.xml has been specified for the resource adapter, it must be a linkref.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199147
The resource adapter only has a weblogic-ra.xml specified. It also needs the ra.xml.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199148
Error Creating Native Lib Directory: {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199149
FileNotFoundException when creating native lib dir for {0}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199150
Failure while creating native library directory for {0}, {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199151
An error occurred while starting the pool: {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199152
test-frequency-seconds is set to non-zero.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199153
Connection testing cannot be enabled for a pool when the ManagedConnectionFactory does not implement ValidatingManagedConnectionFactory. The following invalid settings have been detected:

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199154
Work instance passed in to the Work Manager is null.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199155
The Work Manager is currently not accepting doWork() calls.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199156
The Work Manager is currently suspended. New work is not being accepted.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199157
Unable to establish Execution Context or enlist work in imported transaction, {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199158
Global tx id "{0}" not associated with specified Work instance.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199159
Global tx id "{0}" not registered with the Work Manager.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199160
The <security-principal-map> element was deprecated in WebLogic Server 7.0 and is no longer supported. Please remove the element from the weblogic-ra.xml for the Resource Adapter.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199161
Work instance with global tx id "{0}" already active; conncurrent work disallowed.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199162
Bad ManagedConnectionFactory class specification for class "{0}" : {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199164
Unable to activate the pool, {0}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199165
test-connections-on-create is set to true.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199166
test-connections-on-release is set to true.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199167
test-connections-on-reserve is set to true.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199168
Unable to force log rotation: The connection pool for "{0}" is configured to use the server log.

Category:
Connector

Cause:
Log rotation cannot be forced for pools that are configured to use the server log.

Action:
Change the pool's logging parameters to use a different log other than the server log.

BEA-199169
Failed to get the Connection Factory for the pool "{0}", {1}

Category:
Connector

Cause:
See the details of the error message for more information.

Action:
See the details of the error message for more information.

BEA-199170
For the setting {0}: "{1}" has higher privileges than the deployment user: "{2}".

Category:
Connector

Cause:
The deployment user does not have the privileges to perform the current deployment action.

Action:
Try the deployment action with a user account that has administrator privileges.

BEA-199171
The security-principal-map is not a valid element.

Category:
Connector

Cause:
The security-principal-map is not a valid element. You will need to define the mapping using the Administration Console.

Action:
Define the mapping using the Administration Console.

BEA-199172
The following error occurred in the ra.xml: {0}

Category:
Connector

Cause:
Refer to the text of the message for the description of the problem and the likely cause.

Action:
Correct the problem in the ra.xml file.

BEA-199173
The following error occurred in the weblogic-ra.xml file: {0}

Category:
Connector

Cause:
Refer to the text of the message for the description of the problem and the likely cause.

Action:
Correct the problem in the weblogic-ra.xml file.

BEA-199174
The resource adapter (RA) was deactivated previously when it was in "Suspended" state. The RA cannot be activated again since this will lead to inconsistent state. Redeploy the RA to bring it back to a normal state. Current state: {0}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199175
This ManagedConnection is managed by a container for its transactional behavior and has been enlisted to a JTA transaction by a container; application/adapter must not call the local transaction begin/commit/rollback API. Reject event {0} from adapter.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199176
Unable to execute {1} on ConnectionManager. A stale Connection Factory or Connection Handle may be used. The connection pool associated with it has already been destroyed. Try to perform another lookup of the Connection Factory {0} from JNDI and get a new Connection Handle.

Category:
Connector

Cause:
A stale Connection Factory or Connection Handle was used.

Action:
Perform another lookup of the Connection Factory from JNDI and get a new Connection Handle.

BEA-199177
Trying to deserialize an obsolete ConnectionManager.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199178
Deploy side-by-side versioning of resource adapter with JNDI name {0}; old version: {1}; new version: {2}.

Category:
Connector

Cause:
See the message body.

Action:
No action required.

BEA-199179
This adapter will not be deployed as side-by-side versioning since there is no old version adapter instance deployed.

Category:
Connector

Cause:
No old version adapter instance is currently deployed.

Action:
No action required.

BEA-199180
This application EAR is not deployed in a side-by-side versioning style.

Category:
Connector

Cause:
See the message body.

Action:
No action required.

BEA-199181
Waiting for complete callback from Side-by-side versioning adapter {0}.

Category:
Connector

Cause:
See the message body.

Action:
No action required.

BEA-199182
The resource adapter with module name {0} version {1} called ExtendedBootstrapContext.complete() to indicate it is safe to undeploy.

Category:
Connector

Cause:
The indicated resource adapter is safe to undeploy.

Action:
No action required.

BEA-199183
HintsContext: Ignore unknown hint name [{0}] and its value [{1}].

Category:
Connector

Cause:
An unknown hint was used.

Action:
Inspect the cause and take appropriate action.

BEA-199184
ManagedConnectionFactory of connection pool [{0}] implements javax.resource.spi.TransactionSupport interface. Will use runtime TransactionSupport value [{2}] and igore the value [{1}] configured in DD or annotation.

Category:
Connector

Cause:
A new feature was used, see Section 7.13 of the Connector 1.6 specification.

Action:
No action is required if this behavior is expected.

BEA-199185
There is no META-INF/validation.xml file in the adapter archive {0}. The default Bean Validation configuration will be used.

Category:
Connector

Cause:
No META-INF/validation.xml file was found in the RAR archive.

Action:
No action is required if this behavior is expected.

BEA-199186
Found META-INF/validation.xml in adapter archive {0}.

Category:
Connector

Cause:
A META-INF/validation.xml file was found in the RAR archive.

Action:
No action is required if this behavior is expected.

BEA-199187
Found {2} constraint violation error(s) for {0} on instance [{1}]: {3}

Category:
Connector

Cause:
Bean Validation failed and got constraint violation errors.

Action:
Check the adapter configuration.

BEA-199188
Bean validation failed when validating for {0} on bean instance [{1}]. Exception: {2}

Category:
Connector

Cause:
Bean validation failed.

Action:
Check the adapter configuration and exception details.

BEA-199189
A long-running work submission has been rejected because the count of current active long-running work requests has reached the MaxConcurrentLongRunningRequests limit {0}.

Category:
Connector

Cause:
A long-running work submission was rejected because the count of current active long-running work requests has reached the MaxConcurrentLongRunningRequests limit {0}.

Action:
Check the adapter configuration and increase MaxConcurrentLongRunningRequests if necessary.

BEA-199190
The max-concurrent-long-running-requests limit was changed from {0} to {1}.

Category:
Connector

Cause:
The configuration was changed or initialized.

Action:
No action is required.

BEA-199191
Warning: Caller application {2} defines a shareable resource reference {1} to outbound connection pool {0}, but the pool does not support share by its design either because its

transaction support level is NOTransaction or the ManagedConnectionFactory class has the @Unshareable annotation. Will treat as unshareable.

Category:
Connector

Cause:
An invalid resource reference definition was made to an unshareable ConnectionFactory.

Action:
Change the SharingScope of the resource reference definition to Unshareable.

BEA-199192
Warning: Caller application {2} defines a resource reference {1} to outbound connection pool {0} without defining SharingScope explicitly. The pool does not support share by its design either because its transaction support level is NOTransaction or the ManagedConnectionFactory class has the @Unshareable annotation. Will treat as unshareable.

Category:
Connector

Cause:
An invalid resource reference definition was made to an unshareable ConnectionFactory.

Action:
Change the SharingScope of the resource reference definition to Unshareable.

BEA-199193
ManagedConnection {0} of connectionInfo {1} in Connection Pool {2} has been destroyed already. Previous destroy stacktrace: {3} New destroy stacktrace: {4}

Category:
Connector

Cause:
The ManagedConnection was destroyed again.

Action:
Check the server log.

BEA-199194
Resource adapter generated unexpected exception during work event notification for event {0}. Ignored. Exception: {1}

Category:
Connector

Cause:
The resource adapter generated an unexpected exception during work event notification.

Action:
Check the work event processing codes of the resource adapter.

BEA-199195
Connector annotation scan: Ignored unexpected error [{2}] when processing annotations on {0} while {1}.

Category:
Connector

Cause:
Check the error message and stacktrace to determine the cause.

Action:
Check error message and stacktrace to determine the appropriate action to take.

BEA-199196
Ignore @javax.resource.Connector annotation on class {0} since ResourceAdapter Bean {1} is already specifed in ra.xml.

Category:
Connector

Cause:
ra.xml already specifies the ResourceAdapter bean to use.

Action:
No action is required if this behavior is expected.

BEA-199197
An exception occurred when removing admin object {0}. Exception is: {1}

Category:
Connector

Cause:
This exception occurs as the result of an attempt to unbind the admin object from JNDI.

Action:
Examine the log for the exact exception. Report the error to My Oracle Support.

BEA-199198
An exception occurred when invoking preDestroy on {0}: {1}. Exception is: {1}

Category:
Connector

Cause:
This exception occurs as the result of the CDI container calling the preDestroy method.

Action:
Examine the log for the exact exception. You may need to report the error the resource adapter vendor.

BEA-199199
The work was rejected because it has expired before WorkManager executed it.

Category:
Connector

Cause:
The time value for the startTimeout argument is too short. The WorkManager cannot start the work within the specified time period.

Action:
Increase the time value for the startTimeout argument and ensure that it is big enough for WarkManager to start the work.

BEA-199200
Annotation scan/process of the resource adapter {0} resulted in the following {1} warnings: {2}

Category:
Connector

Cause:
The specified resource adapter failed to pass the annotation scan/process as indicated by the listed warnings.

Action:
Check warning messages and fix the annotations that are involved.

BEA-199201
Failed to merge resource adapter {0} when processing annotations due to {1} error(s) found.

Category:
Connector

Cause:
Failed to merge resource adapter {0} when processing annotations due to {1} error(s) found.

Action:
Check the errors and fix them.

BEA-199202
Ignored unexpected exception [{1}] when unregistering runtime mbean {0}.

Category:
Connector

Cause:
Check error message and stack trace to figure out the cause.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-199211
Compliance checking and validation of the resource adapter {0} resulted in the following non-critical errors: {1}

Category:
Connector

Cause:
The specified resource adapter failed to pass compliance and validity checking as indicated by the listed warnings and errors.

Action:
Correct the ra.xml or weblogic-ra.xml files, or check the resource adapter archive.

BEA-199212
Failed to create connection pool [{0}] due to error: {1}

Category:
Connector

Cause:
Check the reported error message and stack trace to determine the cause.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-199213
A new error occurred when trying to destroy a connection pool [{0}] that was previously in a failed state : the following new error will be ignored: {1}

Category:
Connector

Cause:
Check the error message and stack trace to determine the cause.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-199214
The connection pool [{0}] was in a HEALTH_CRITICL state already, therefore this method call is not allowed.

Category:
Connector

Cause:
Check the error message and stack trace to determine the cause.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-199215
The connection pool [{0}] will move to a HEALTH_CRITICAL state because the adapter is not in deploy-as-a-whole mode. This pool failed due to errors: {1}

Category:
Connector

Cause:
Check the error message and stack trace to determine the cause.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-199216
An error occurred when performing action {2} on connection pool [{0}]. The following error will be ignored: {1}

Category:
Connector

Cause:
Check the error message and stack trace to determine the cause.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-199217
Connection pool [{0}] has validation errors and cannot be reset. Try to fix all validation errors and then do a dynamic update or redeploy this adapter.

Category:
Connector

Cause:
Check the error message and stack trace to determine the cause.

Action:
Try to fix all validation errors and then do a dynamic update or redeploy this adapter.

BEA-199218
Unable to determine whether properties were changed for Connection pool [{0}]. If there are changed properties, they may be ignored during a dynamic update: {1}

Category:
Connector

Cause:
Check the error message and stack trace to determine the cause.

Action:
Try to fix all validation errors and then do a dynamic update or redeploy this adapter.

BEA-199219
Invalid shrink threshold value {0} specified for the system property weblogic.connector.cmm.shrinkThreshold. Value must be between 0 and 10 (inclusive).

Category:
Connector

Cause:
The value of the system property weblogic.connector.cmm.shrinkThreshold is invalid.

Action:
Check the value of the system property weblogic.connector.cmm.shrinkThreshold. Ensure that it is between 0 and 10 (inclusive). A value of 0 indicates that the connector will not take any action on any memory pressure level.

BEA-199220
Failed to parse the string for UniversalResourceKey: {0}.

Category:
Connector

Cause:
The UniversalResourceKey string representation is incorrect.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-199221
Failed to parse the defining application information for UniversalResourceKey: {0}.

Category:
Connector

Cause:
The UniversalResourceKey string representation is incorrect.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-199222
The UniversalResourceKey is defined by application information: {1}#{2}#{3}, but its JNDI name {0} has the wrong name space.

Category:
Connector

Cause:
An application-defined resource has an invalid JNDI name.

Action:
Check the name field of @ConnectionFactoryDefinition/@AdministeredObjectDefinition or the equivalent deployment descriptor element. Ensure that it has a valid JNDI name space.

BEA-199223
The name space of a JNDI name {0} does not match its application information: {1}#{2}#{3}

Category:
Connector

Cause:
An application-defined resource has an invalid JNDI name.

Action:
Check the name field of @ConnectionFactoryDefinition/@AdministeredObjectDefinition or the equivalent deployment descriptor element. Ensure that it has a valid JNDI name space.

BEA-199224
JNDI name {0} has prefix of 'java:', but has no defining application information.

Category:
Connector

Cause:
An invalid JNDI name was specified for a resource.

Action:
Check the jndi-name field of the resource and ensure that it has a valid JNDI name.

BEA-199300
Cannot find Connection Definition via interfaceName:{0} from Resource Adapter:{1}. The application information: {2}#{3}#{4} The JNDI name:{5}

Category:
Connector

Cause:
The interfaceName field may be filled incorrectly for the ConnectionFactoryDefinition annotiation or the equivalent deployment descriptor.

Action:
Use the correct interfaceName for the ConnectionFactoryDefinition annotation or the equivalent deployment descriptor.

BEA-199301
Cannot find AdminObject definition in Resource Adapter {0} with className: {1} and interfaceName: {2} The application information: {3}#{4}#{5} The JNDI name:{6}

Category:
Connector

Cause:
Either the className field or the interfaceName field contains an incorrect value.

Action:
Fill the className or interfaceName field or both with the correct value.

BEA-199302
Cannot determine the AdminObject interface from class:{0} from Resource Adapter:{1} The application information: {2}#{3}#{4} The JNDI name:{5}

Category:
Connector

Cause:
1. The interfaceName field has no entry. 2. An incorrect className field was used for AdminObject.

Action:
1. Fill the interfaceName field with a valid value. 2. Fill the className field with the correct value.

BEA-199303
The connector resource {4} is defined in application: {1}#{2}#{3}. The corresponding resource adapter {0} is not globally accessible and is not in the same application with {1}.

Category:
Connector

Cause:
The resource adapter's deployment descriptor is not accessible from the component that defines the connector resource.

Action:
1. Use another resource adapter for the connector resource. 2. Update the resource adapter's deployment descriptor, and ensure that it is accessible from the component that defines the connector resource.

BEA-199304
Failed to export object of class:{0} from Resource Adapter:{1} The application information: {2}#{3}#{4} The JNDI name:{5}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199305
Duplicated resource definition for Resource Adapter:{0} The application information: {1}#{2}#{3} The JNDI name:{4}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199306
At least one application-defined resource is found for Resource Adapter:{0} The application information: {1}#{2}#{3} The JNDI name:{4}

Category:
Connector

Cause:
The resource adapter cannot be undeployed when an application-defined resource exists.

Action:
Undeploy the application first.

BEA-199307
Failed to unexport object: {0} which JNDI name is {1}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199308
Failed to find PartitionRuntimeMBean for the partition {0}.

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199309
Unable to register runtime MBean for connector: {0}.

Category:
Connector

Cause:
The runtime MBean cannot be registered. See the reported error for the cause.

Action:
Examine the exception in the log for more information about how to correct the problem.

BEA-199310
Failed to lookup JNDI name: {3}. This resource is defined in application: {0}#{1}#{2}.

Category:
Connector

Cause:
The corresponding resource adapter may not be activated.

Action:
Check the status of the corresponding resource adapter and activate it or take other appropriate action.

BEA-199311
Failed to find Resource Adapter:{0} The application information: {1}#{2}#{3} The JNDI name: {4}

Category:
Connector

Cause:
Check the logs for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199312
At least one of the permissions declared in permissions.xml is not allowed.

Category:
Connector

Cause:
Check the permissions.xml configuration for the cause of this exception.

Action:
Inspect the cause and take appropriate action.

BEA-199313
Application classloader is used for loading resource adaptor {1}"s classes in application {0}.

Category:
Connector

Cause:
<enable-ee-compliant-classloading-for-embedded-adapters> is set to true.

Action:
No action is required.

BEA-199314
Resource adaptor"s classloader is used for loading resource adaptor {1}"s classes in application {0}. This classloader is the child classloader of the application classloader.

Category:
Connector

Cause:
<enable-ee-compliant-classloading-for-embedded-adapters> is set to false.

Action:
No action is required.

BEA-199315
The <classloader-structure> configuration in application {0}"s weblogic-application.xml is ignored by resource adapter {1} because resource adapter {1}"s <enable-global-access-to-classes> is set to true.

Category:
Connector

Cause:
<enable-global-access-to-classes> is set to true.

Action:
No action is required.

BEA-199316
Failed to destroy pool [{0}] due to error: {1}

Category:
Connector

Cause:
Check the reported error message and stack trace to determine the cause.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-199317
Failed to create admin object [{0}] due to error: {1}

Category:
Connector

Cause:
Check the reported error message and stack trace to determine the cause.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-199318
It is not supported to access connector resource outside server {0} which defines the resource, current server is {1}.

Category:
Connector

Cause:
Check the reported error message and stack trace to determine the cause.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-199319
It is not supported to access resource adapter outside partition {0} which defines the resource, current partition is {1}.

Category:
Connector

Cause:
Check the reported error message and stack trace to determine the cause.

Action:
Take appropriate action based on the cause determined from the reported error message and stack trace.

BEA-200000
Failed to initialize the messaging bridge service.

Category:
MessagingBridge

Cause:
Most of the time, this results from configuration errors.

Action:
Check the configuration file and reboot the system.

BEA-200001
The messaging bridge service has successfully shut down.

Category:
MessagingBridge

Cause:
This message indicates that the messaging bridge service has been shut down, either at the request of the administrator or due to errors.

Action:
No action is required.

BEA-200002
Failed to deploy the messaging bridge "{0}" because the messaging bridge service is shut down.

Category:
MessagingBridge

Cause:
This message indicates that the messaging bridge service has been shut down, either at the request of the administrator or due to errors.

Action:
Reboot the system.

BEA-200003
Failed to deploy the messaging bridge "{0}" due to error: {1}.

Category:
MessagingBridge

Cause:
This is likely due to configuration errors or an internal WebLogic Server error as indicated in the message body.

Action:
Check the configuration file, and reboot the server.

BEA-200004
The messaging bridge "{0}" has been successfully deployed.

Category:
MessagingBridge

Cause:
This message indicates that the messaging bridge has been successfully deployed.

Action:
No action is required.

BEA-200005
Failed to start messaging bridge "{0}" due to error: {1}

Category:
MessagingBridge

Cause:
This is likely due to configuration errors or an internal WebLogic Server error, as indicated in the message body.

Action:
Check the configuration file, and reboot the server.

BEA-200008
Bridge "{0}" does not have a configured source destination.

Category:
MessagingBridge

Cause:
This is likely due to configuration errors.

Action:
Update the configuration, and restart the server.

BEA-200009
Bridge "{0}" does not have a configured target destination.

Category:
MessagingBridge

Cause:
This is likely due to configuration errors.

Action:
Update the configuration, and restart the server.

BEA-200011
The bridge "{0}" failed to find the adapter "{1}". The bridge will periodically retry to look up the adapter. If this message stops reappearing, it means that the bridge has finally successfully found the adapter.

Category:
MessagingBridge

Cause:
One of the adapters was not deployed.

Action:
Deploy the required adapters.

BEA-200012
Bridge "{0}" successfully found the adapters that are configured for it.

Category:
MessagingBridge

Cause:
This message indicates that the bridge successfully found the adapters.

Action:
No action is required.

BEA-200013
Invalid properties are defined for the source destination of bridge "{0}".

Category:
MessagingBridge

Cause:
The configuration was invalid.

Action:
Update the configuration, and restart the server.

BEA-200014
Invalid properties are defined for the target destination of bridge "{0}".

Category:
MessagingBridge

Cause:
The configuration was invalid.

Action:
Update the configuration, and restart the server.

BEA-200015
An error occurred in bridge "{0}" during the transfer of messages ({1}).

Category:
MessagingBridge

Cause:
An error occurred on one of the bridge destinations.

Action:
Check the system on both the source and target sides, and restart the server.

BEA-200020
Bridge "{0}" is stopped.

Category:
MessagingBridge

Cause:
This message indicates that the messaging bridge has stopped.

Action:
No action is required.

BEA-200021
Bridge "{0}" failed to get one of the adapters from JNDI ({1}).

Category:
MessagingBridge

Cause:
At least one adapter was not deployed when the bridge started. It is also possible that the JNDI names configured in the bridge destinations do not match the ones in the adapter deployment descriptor file.

Action:
Check to see if the adapter(s) required by the source and target destinations are deployed on the server where the bridge is configured. Ensure that the JNDI name in the adapter deployment descriptor file matches the one in the configuration of the bridge destinations. Otherwise, no action is required. The bridge will automatically try again later.

BEA-200022
Bridge "{0}" failed to obtain adapter metadata ({1}).

Category:
MessagingBridge

Cause:
This is an internal WebLogic Server error that should not occur.

Action:
No action is required.

BEA-200024
Bridge "{0}" refused to obtain connections and transfer any messages, because it has been stopped, suspended, or is shutting down.

Category:
MessagingBridge

Cause:
The administrator has shut down or stopped the bridge, or the bridge is suspended for migration.

Action:
No action is required.

BEA-200025
Bridge "{0}" failed to start because the quality of service configured ({1}) is unreachable. This is likely due to an invalid configuration or adapter limitations.

Category:
MessagingBridge

Cause:
The configuration does not match the ability of the adapters and underlying systems.

Action:
Change the configuration of the bridge with a reachable quality of service, or turn on the QOSDegrationAllowed boolean.

BEA-200026
Bridge "{0}" encountered problems in one of its adapters or underlying systems. It stopped transferring messages and will try to reconnect to the adapters shortly. (The exception that occurred was {1})

Category:
MessagingBridge

Cause:
There was a problem in receiving or sending messages to one of the sides of the bridge.

Action:
No action is required.

BEA-200027
Bridge "{0}" works in asynchronous mode and has not received messages for the predefined maximum idle time. The connections to the adapters will be interrupted and reestablished.

Category:
MessagingBridge

Cause:
This may occur because the source destination is empty or because the connection to the source was stale and needs to be reestablished.

Action:
Check the source system.

BEA-200028
The bridge "{0}" has started transferring messages.

Category:
MessagingBridge

Cause:
This message indicates that the bridge has just started transferring messages.

Action:
No action is required.

BEA-200030
Bridge "{0}" is configured to work in "{1}" mode, but it is actually working in "{2}" mode.

Category:
MessagingBridge

Cause:
This message reveals what quality of service the bridge is actually providing.

Action:
No action is required.

BEA-200031
Bridge "{0}" is configured to allow degradation of its quality of service in cases where the configured quality of service cannot be reached.

Category:
MessagingBridge

Cause:
This message indicates that the quality of service of this bridge is allowed to be downgraded if the required one is unreachable.

Action:
No action is required.

BEA-200032
Bridge "{0}" is configured to disallow degradation of its quality of service in cases where the configured quality of service is unreachable.

Category:
MessagingBridge

Cause:
This message indicates that the quality of service of the bridge is not allowed to be downgraded.

Action:
No action is required.

BEA-200033
Bridge "{0}" is obtaining connections to the two adapters.

Category:
MessagingBridge

Cause:
This message indicates that the messaging bridge is obtaining connections to the two adapters.

Action:
No action is required.

BEA-200034
Bridge "{0}" is shut down.

Category:
MessagingBridge

Cause:
This message indicates that the messaging bridge is shut down.

Action:
No action is required.

BEA-200035
Bridge "{0}" has been started from the stopped mode.

Category:
MessagingBridge

Cause:
This message indicates that the bridge was in stopped mode and has just been restarted.

Action:
No action is required.

BEA-200036
The started attribute of bridge "{0}" has been changed from "{1}" to "{2}".

Category:
MessagingBridge

Cause:
This is due to a configuration change.

Action:
No action is required.

BEA-200037
The "{1}" attribute of bridge "{0}" has been changed from "{2}" to "{3}".

Category:
MessagingBridge

Cause:
This is due to a configuration change.

Action:
No action is required.

BEA-200038
Bridge "{0}" is inactive because it is configured to be stopped.

Category:
MessagingBridge

Cause:
The bridge is configured to be stopped.

Action:
No action is required.

BEA-200039
Bridge "{0}" has the same destination as its source and target.

Category:
MessagingBridge

Cause:
This is due to a configuration error.

Action:
Update the configuration.

BEA-200040
Bridge destination {0}: connection URL cannot be null if the initial context factory is not weblogic.jndi.WLInitialContextFactory.

Category:
MessagingBridge

Cause:
This is due to a configuration error.

Action:
Update the configuration.

BEA-200041
Bridge destination {0}: a bridge destination for JMS must have a connection factory JNDI name and a destination JNDI name configured.

Category:
MessagingBridge

Cause:
This is due to a configuration error.

Action:
Update the configuration.

BEA-200042
Bridge {0} failed to connect to the source destination and will try again in {2} seconds. This could be a temporary condition unless the messages repeat several times. ({1})

Category:
MessagingBridge

Cause:
An error occurred on the source destination of the bridge. The error may occur because the source destination does not exist or has not been active yet.

Action:
Check the source system and its configuration. Ensure that the destination is configured in the system and the system is running.

BEA-200043
Bridge "{0}" failed to connect to the target destination and will try again in {2} seconds. This could be a temporary condition unless the messages repeat several times. ({1})

Category:
MessagingBridge

Cause:
The error occurred on the target destination of the bridge. The error may occur because the target destination does not exist or has not been active yet.

Action:
Check the target system and its configuration. Ensure that the destination is configured in the system and the system is running.

BEA-200044
The following exception has occurred:

Category:
MessagingBridge

Cause:
An error condition has occurred.

Action:
Look for the associated exception in the log or the program to see the results. In general, this stack trace will help in debugging an existing problem.

BEA-200045
Bridge "{0}" failed to start because it has been suspended or is shutting down.

Category:
MessagingBridge

Cause:
The administrator has shut down the bridge, or the bridge is suspended for migration.

Action:
No action is required.

BEA-200046
The "{1}" attribute of bridge "{0}" has been changed from "{2}" to "{3}".

Category:
MessagingBridge

Cause:
This is due to a configuration change.

Action:
No action is required.

BEA-200047
Bridge "{0}" failed to start because its migratable target has not been activated for this server.

Category:
MessagingBridge

Cause:
The bridge is targeted to a migrable target that has not yet been activated on this server.

Action:
No action is required.

BEA-200048
{1} destination "{2}" of bridge "{0}" has a configured adapter JNDI name "{3}", so it will find the internal automatically deployed adapter with JNDI name "{4}". The bridge will ignore an explicitly configured and deployed adapter with adapter JNDI name "{3}". The deployed adapter will be ignored, the bridge does not need to deploy a separate adapter.

Category:
MessagingBridge

Cause:
This is due to a configuration upgrade.

Action:
No action is required.

BEA-200049
{1} destination "{2}" of bridge "{0}" uses a custom adapter JNDI name "{3}" instead of the expected names of eis.jms.WLSConnectionFactoryJNDIXA or eis.jms.WLSConnectionFactoryJNDINOXA.

Category:
MessagingBridge

Cause:
The bridge destination uses a configured adapter JNDI name.

Action:
No action is required.

BEA-200050
The bridge has a configured adapter JNDI name "{1}", so it will find the internal automatically deployed adapter with JNDI name "{2}". The bridge will ignore an explicitly configured and deployed adapter "{0}". The deployed adapter will be ignored.

Category:
MessagingBridge

Cause:
The bridge destination uses a configured adapter.

Action:
No action is required.

BEA-210000
{0}

Category:
COM

Cause:
See the message body.

Action:
Correct the error.

BEA-210001
{0}

Category:
COM

Cause:
See the message body.

Action:
No action is required.

BEA-210003
No network channel is available to handle COM requests.

Category:
COM

Cause:
The server is not configured with at least one non-SSL port.

Action:
Configure a plain text listener port if COM is enabled.

BEA-213500
Partition {0} has ResourceDeploymentPlanPath set to {1} but the zip file from which it is being imported does not have an entry for it.

Category:
Partition Portability

Cause:
While importing the paritition, an attempt was made to import a partition without proper configuration. The element resource-deployment-plan-path points to a plan which is to be used for overwriting resource attributes. As part of exporting a partition, this plan should have been archived as part of the overall partition archive created, but the exported archive is missing the plan.

Action:
Export the partition once again and verify that the exported archive ZIP file contains the file referred to by <resource-deployment-plan-path > in config.xml before importing the partition.

BEA-213501
Could not find partition by name {0} to export in the current domain.

Category:
Partition Portability

Cause:
The partition name that was provided for export does not exist in the domain.

Action:
Check the name of the partition and then run exportPartition again.

BEA-213502
A ResourceGroupTemplate with name {0} already exists.

Category:
Partition Portability

Cause:
This error occurs if importPartition is called with the createNew parameter set to null, and the partition being imported references a ResourceGroupTemplate that has the same name as one of the ResourceGroupTemplates in the domain.

Action:
If you want to use the existing ResourceGroupTemplate, run importPartition again with createNew set to false. If you want to clone the ResourceGroupTemplate with a new name, run importPartition again with createNew set to true.

BEA-213503
Could not delete temporary pending file {0}.

Category:
Partition Portability

Cause:
During import, if the option createNew is set to false, then it is imperative that the files corresponding to the ResourceGroupTemplate copied into the pending directory as part of import be deleted before activate is called.

Action:
Delete the file {0} and run importPartition again.

BEA-213504
The destination for writing imported app {0} already exists at {1}.

Category:
Partition Portability

Cause:
While importing a partition with the application binaries/plan, the destination for writing the binary/plan file in an imported domain file system already has a file with the same name.

Action:
Delete the file in the domain at {1} and run importPartition again.

BEA-213505
Application {0} with staging mode set to {1} does not exist at the specified sourcepath {2}.

Category:
Partition Portability

Cause:
The imported partition references an application that is neither in the exported ZIP file nor at the specified location as specified by the source-path attribute of the app-deployment bean.

Action:
Check that source-path is correct and run importPartition again after placing the application binary at the specified source-path.

BEA-213506
The application {0} has the stagingMode set to {1} but the exported ZIP file does not have application binaries to import.

Category:
Partition Portability

Cause:
The imported partition references an application that is in {1} staged mode. The exported ZIP file does not, however, contain the application binary.

Action:
Either change the staging mode in the attributes.json file to external_stage/nostage or export again with the application binaries included.

BEA-213507
attributes.json has a reference attribute {0} with its value set to {1}, but this attribute was not found in the imported domain"s configuration.

Category:
Partition Portability

Cause:
A wrong attributes value was specified in the attributes.json file during importPartition.

Action:
Look at config.xml before importing and use the proper attribute values for updating attributes.json before importing the partition.

BEA-213508
The name of the object {0} in partition-config.xml is {1} whereas {2} has the name changed to something else. Therefore it could not be found. Changing names of attributes in {2} is not supported.

Category:
Partition Portability

Cause:
The name of an attribute was changed in {2}.

Action:
Revert the name change in {2} and importPartition again.

BEA-213509
Partition {0} is in an unknown state because of a non-dynamic change that was made which affects {1}. The server must be rebooted in order for the partition to become stable and export Partition to work.

Category:
Partition Portability

Cause:
The partition being exported is in an unknown state. A common cause of this is that a non-dynamic configuration change was made to the domain that has deferred the initialization of the partition until the Administration Server is restarted.

Action:
Restart the Administration Server.

BEA-213510
{0} for partition {1} failed.

Category:
Partition Portability

Cause:
TBD

Action:
Look at the stack trace and fix appropriate error.

BEA-213511
{0} for partition {1} succeeded.

Category:
Partition Portability

Cause:
TBD

Action:
TBD

BEA-240001
{0}

Category:
Console

Cause:
The Administration Console logs informational messages about console usage.

Action:
No action is required.

BEA-240002
{0}

Category:
Console

Cause:
The Administration Console encountered an error that is potentially harmful.

Action:
Review the warning message text to determine the appropriate action.

BEA-240003
Administration Console encountered the following error: {0}

Category:
Console

Cause:
The Administration Console encountered an error, but the console may continue to run.

Action:
Review the error message text to determine the appropriate action.

BEA-240004
The Administration Console encountered the following error: {0}

Category:
Console

Cause:
The Administration Console encountered a critical error.

Action:
Review the message text to determine the appropriate action.

BEA-240005
A Cross-site Request Forgery (CSRF) has been detected. Task={0}, address={1}, user={2}

Category:
Console

Cause:
The Administration Console encountered a CSRF.

Action:
Take action based upon the provided exception details.

BEA-260000
WebLogic Local Deployment Manager

Category:
J2EE Deployment SPI

Cause:
This is an informational message.

Action:
No action is required.

BEA-260001
"{0}" does not identify a known Deployment Manager. The URI must be of the form: deployer:WebLogic:host:port. The host and port are required if attempting to acquire a connected Deployment Manager.

Category:
J2EE Deployment SPI

Cause:
An invalid URI was provided when allocating a Deployment Manager.

Action:
No action is required.

BEA-260002
"{0}" is not a valid URI. The URI must be of the form: "deployer:WebLogic:protocol://host:port". The host and port are required if attempting to acquire a connected Deployment Manager. The protocol should be a well-known IP protocol.

Category:
J2EE Deployment SPI

Cause:
Incorrect host/port used when attempting to allocate a Deployment Manager.

Action:
No action is required.

BEA-260003
Feature not available when in disconnected mode.

Category:
J2EE Deployment SPI

Cause:
A deployment tool allocated a disconnected Deployment Manager or released it.

Action:
Allocate a connected Deployment Manager.

BEA-260004
Locale, "{0}", is not supported.

Category:
J2EE Deployment SPI

Cause:
The locale was incorrectly specified.

Action:
No action is required.

BEA-260008
J2EE version {0} not supported by this Deployment Manager.

Category:
J2EE Deployment SPI

Cause:
An invalid argument was used.

Action:
No action is required.

BEA-260009
Exception caught for class "{0}" while attempting to create Deployment Manager: {1}

Category:
J2EE Deployment SPI

Cause:
See the message body.

Action:
No action is required.

BEA-260010
Unable to connect to "{0}" as user, "{1}". Error received: {2}

Category:
J2EE Deployment SPI

Cause:
Authorization failed.

Action:
No action is required.

BEA-260012
No configured targets match provided target with name, "{0}", and type, "{1}"

Category:
J2EE Deployment SPI

Cause:
An invalid argument was used.

Action:
No action is required.

BEA-260013
The target array passed to Deployment Manager was null or empty.

Category:
J2EE Deployment SPI

Cause:
An invalid argument was used.

Action:
No action is required.

BEA-260015
The "{0}" operation is not supported.

Category:
J2EE Deployment SPI

Cause:
An invalid request was made; the operation is not supported.

Action:
No action is required.

BEA-260016
"{0}" does not exist.

Category:
J2EE Deployment SPI

Cause:
An invalid argument was used.

Action:
No action is required.

BEA-260017
Unable to locate deployment task, "{0}"

Category:
J2EE Deployment SPI

Cause:
The task was removed from the system.

Action:
No action is required.

BEA-260020
Module {1} of application {0} successfully transitioned from {2} to {3} on server {4}.

Category:
J2EE Deployment SPI

Cause:
This is an informational message.

Action:
No action is required.

BEA-260021
Module {1} of application {0} failed to transition from {2} to {3} on server {4}.

Category:
J2EE Deployment SPI

Cause:
This is an informational message.

Action:
No action is required.

BEA-260022
{2} application {0} on server {1}.

Category:
J2EE Deployment SPI

Cause:
This is an informational message.

Action:
No action is required.

BEA-260023
Deployment task does not exist for ProgressObject

Category:
J2EE Deployment SPI

Cause:
The deployment task was removed from the system.

Action:
No action is required.

BEA-260024
Connection errors occurred while reporting a progress event. The event was from application, {0}, module, {1}, on server {2}. The event was {3}. The error was {4}.

Category:
J2EE Deployment SPI

Cause:
There was a deployment failure.

Action:
No action is required.

BEA-260026
Task failed for unknown reason. Task description is {0}

Category:
J2EE Deployment SPI

Cause:
The cause is unknown.

Action:
No action is required.

BEA-260027
Non-root module, "{1}", is not supported for {0} operations. All modules must represent root modules.

Category:
J2EE Deployment SPI

Cause:
All modules must represent root modules. This operation does not support embedded modules.

Action:
Use DeploymentManager.enableModuleTargeting.

BEA-260028
No targeting information was provided for {0} operation.

Category:
J2EE Deployment SPI

Cause:
An invalid argument was used.

Action:
No action is required.

BEA-260029
"{1}" is not part of application, "{2}". Only one application allowed for {0} operation.

Category:
J2EE Deployment SPI

Cause:
Multiple applications were specified in the same operation. An invalid argument was used.

Action:
No action is required.

BEA-260030
Module, "{0}", is not part of any application.

Category:
J2EE Deployment SPI

Cause:
An invalid argument was used.

Action:
No action is required.

BEA-260031
No action performed or required for {0} request.

Category:
J2EE Deployment SPI

Cause:
This is an informational message.

Action:
No action is required.

BEA-260036
Module type, "{0}", is not supported.

Category:
J2EE Deployment SPI

Cause:
The operation is unsupported.

Action:
No action is required.

BEA-260037
Encountered unexpected descriptor for module "{0}".

Category:
J2EE Deployment SPI

Cause:
An invalid application descriptor was used in the EAR file.

Action:
Fix the application descriptor.

BEA-260040
No files provided in {0} request.

Category:
J2EE Deployment SPI

Cause:
At least one file must be specified for update.

Action:
No action is required.

BEA-260041
Unable to upload "{1}" to "{0}"

Category:
J2EE Deployment SPI

Cause:
Check the log for further details. Requested files need to be uploaded to a remote Administration Server.

Action:
No action is required.

BEA-260050
"{0}" does not implement weblogic.deploy.api.spi.WebLogicDConfigBeanRoot, or cannot be instantiated: {1}.

Category:
J2EE Deployment SPI

Cause:
See the message body.

Action:
Check for other log messages that give more information about the failure.

BEA-260052
null DConfigBeanRoot.

Category:
J2EE Deployment SPI

Cause:
An invalid argument was used.

Action:
No action is required.

BEA-260055
Unable to parse deployment plan: "{0}".

Category:
J2EE Deployment SPI

Cause:
The document is invalid and could not be read or parsed during a deployment operation.

Action:
No action is required.

BEA-260056
MBean must be for Application or Component: "{0}".

Category:
J2EE Deployment SPI

Cause:
An invalid argument was used.

Action:
No action is required.

BEA-260061
Unable to recognize DDBean with xpath, "{0}".

Category:
J2EE Deployment SPI

Cause:
Unable to restore configuration from an invalid descriptor; an invalid argument was used.

Action:
No action is required.

BEA-260067
Restored configuration for module, {0}

Category:
J2EE Deployment SPI

Cause:
DeploymentConfiguration.restoreDConfigBean was invoked

Action:
No action is required.

BEA-260068
Removed configuration for module, {0}

Category:
J2EE Deployment SPI

Cause:
DeploymentConfiguration.removeDConfigBean was invoked.

Action:
No action is required.

BEA-260070
Saved configuration for module, {0}

Category:
J2EE Deployment SPI

Cause:
DeploymentConfiguration.saveDConfigBean was invoked.

Action:
No action is required.

BEA-260071
Restored configuration for application, {0}

Category:
J2EE Deployment SPI

Cause:
DeploymentConfiguration.restore was invoked.

Action:
No action is required.

BEA-260072
Saved configuration for application, {0}

Category:
J2EE Deployment SPI

Cause:
DeploymentConfiguration.save was invoked.

Action:
No action is required.

BEA-260073
Unable to introspect on bean, "{0}".

Category:
J2EE Deployment SPI

Cause:
See the message detail.

Action:
No action is required.

BEA-260078
No DConfigBean is available for invalid module, "{0}": {1}.

Category:
J2EE Deployment SPI

Cause:
Check the error message for the specific problem.

Action:
No action is required.

BEA-260080
Unable to define the application install directory at "{0}". Directory could not be created or is a file.

Category:
J2EE Deployment SPI

Cause:
The directory could not be created or is a file.

Action:
Specify a valid directory.

BEA-260081
The descriptor at "{0}" could not be parsed.

Category:
J2EE Deployment SPI

Cause:
The descriptor contains syntax errors and is invalid.

Action:
No action is required.

BEA-260082
A required descriptor, {0}, for a CMP bean is missing.

Category:
J2EE Deployment SPI

Cause:
A descriptor file is missing.

Action:
Place the necessary descriptor file in the archive file or its external configuration area.

BEA-260083
No plan document at "{0}"

Category:
J2EE Deployment SPI

Cause:
The path for the plan may have been incorrectly specified. If this is the first time the application is being configured; this may not be a problem; the plan will be created.

Action:
Specify the correct plan location as necessary.

BEA-260085
The configuration descriptor for "{0}" already exists ({1}), or was not modified ({2}), and will not be saved.

Category:
J2EE Deployment SPI

Cause:
The descriptors do not need to be saved.

Action:
No action is required.

BEA-260086
The descriptor information at {0} was saved to the configuration area.

Category:
J2EE Deployment SPI

Cause:
The configuration was saved.

Action:
No action is required.

BEA-260087
The descriptor at "{0}" is missing the required {1} element for custom module with URI, "{2}", and provider, "{3}".

Category:
J2EE Deployment SPI

Cause:
The named element is missing from the weblogic-extensions.xml descriptor.

Action:
Correct the errors in the weblogic-extensions.xml descriptor.

BEA-260088
The {1} descriptor at "{0}" is missing.

Category:
J2EE Deployment SPI

Cause:
The referenced JMS/JDBC descriptor is not present in the archive.

Action:
Ensure that all of the descriptors are in place.

BEA-260091
Errors were detected when reading "{0}": {1}

Category:
J2EE Deployment SPI

Cause:
Check the error message to determine the probable cause.

Action:
No action is required.

BEA-260094
Registering config module descriptor support with base URI, {0}, and configuration URI, {1}.

Category:
J2EE Deployment SPI

Cause:
The weblogic-extensions descriptor specified custom configuration descriptor support.

Action:
No action is required.

BEA-260095
Unable to create archive for "{0}"

Category:
J2EE Deployment SPI

Cause:
An attempt to name a file with the appropriate extension failed.

Action:
No action is required.

BEA-260096
Unable to determine type of application for "{0}".

Category:
J2EE Deployment SPI

Cause:
The archive does not contain standard descriptors.

Action:
Ensure that the correct file was passed into the deployment operation.

BEA-260097
Unable to understand DDBeanRoot provided by deployer tool: "{0}".

Category:
J2EE Deployment SPI

Cause:
The model API is not providing the expected information

Action:
Resolve API problems in the class that implements javax.enterprise.deploy.model.DDBeanRoot.

BEA-260098
No descriptor type is registered for modules of type, {0}

Category:
J2EE Deployment SPI

Cause:
The module type is not registered with a configurable descriptor.

Action:
Register non-standard descriptors using the weblogic-extension.xml descriptor.

BEA-260099
No root element in {0} descriptor, {1} at {2}.

Category:
J2EE Deployment SPI

Cause:
An invalid deployment descriptor was provided for the module.

Action:
Either the wrong descriptor was specified or the module type is incorrect; take the appropriate actions to fix the problem.

BEA-260100
Invalid value for Security Model, {0}; Should be one of {1}.

Category:
J2EE Deployment SPI

Cause:
An unrecognized security model was requested.

Action:
Use a valid security model

BEA-260101
Parameter "{0}" may not be null.

Category:
J2EE Deployment SPI

Cause:
A null parameter was passed to the method.

Action:
Resolve the client programming error.

BEA-260102
Type parameter, "{0}", provided to export method is invalid

Category:
J2EE Deployment SPI

Cause:
An invalid export type parameter was used.

Action:
Use a valid export type.

BEA-260103
The provided bean is not part of this configuration: "{0}".

Category:
J2EE Deployment SPI

Cause:
An attempt was made to export bean properties against the wrong DConfigBeanRoot object

Action:
Invoke export on the correct DConfigBeanRoot.

BEA-260104
{0} is not a changable property

Category:
J2EE Deployment SPI

Cause:
One of the properties is not changeable.

Action:
Remove the property that is not changeable from the list.

BEA-260106
Failed to parse descriptor at "{1}" for module "{0}": {2}.

Category:
J2EE Deployment SPI

Cause:
The descriptor is not valid

Action:
Ensure that the application is accessible and contains valid descriptors.

BEA-260107
Failed to write descriptor for module "{0}" configuration: {1}.

Category:
J2EE Deployment SPI

Cause:
Either an I/O error prevented the save operation or the descriptor is missing some required elements.

Action:
Depends on the specific error. See the error message for details.

BEA-260108
Failed to restore descriptors: {0}.

Category:
J2EE Deployment SPI

Cause:
An I/O or parse error prevented the restore operation.

Action:
The course of action depends on the specific error. See the error message for details.

BEA-260109
Failed to write deployment plan: {0}.

Category:
J2EE Deployment SPI

Cause:
Either an I/O error prevented the save operation or the plan is missing some required elements.

Action:
The course of action depends on the specific error; see the error message for details.

BEA-260110
Failed to create configuration for module: {0}

Category:
J2EE Deployment SPI

Cause:
The configuration artifacts for the application could not be processed. This could result from simple access errors, descriptor parsing failures, or basic application architecture problems.

Action:
The course of action depends on the specific error. See the error message for details.

BEA-260111
Errors were detected while attempting to communicate with the Administration Server.

Category:
J2EE Deployment SPI

Cause:
Depends on the specific error. The associated exception will contain the root exception.

Action:
The course of action depends on the specific error. See the exception.

BEA-260112
Unable to determine application name from null or empty TargetModuleID list.

Category:
J2EE Deployment SPI

Cause:
No TargetModuleID objects were provided.

Action:
Resolve the client programming error by providing a list of TargetModuleID objects.

BEA-260113
Plan at "{0}" is a directory. A deployment plan is always an XML document.

Category:
J2EE Deployment SPI

Cause:
Plan at "{0}" is a directory, not an XML document.

Action:
Resolve the client programming error.

BEA-260114
Application root at "{0}" is not a directory.

Category:
J2EE Deployment SPI

Cause:
An invalid root directory was specified.

Action:
Resolve the client programming error.

BEA-260115
Must specify application to configure.

Category:
J2EE Deployment SPI

Cause:
No application was specified for the configuration.

Action:
Resolve the client programming error.

BEA-260116
Configuration is not initialized

Category:
J2EE Deployment SPI

Cause:
SessionHelper.initialize() was not yet invoked.

Action:
Resolve the client programming error.

BEA-260117
Unable to load factory, "{0}"

Category:
J2EE Deployment SPI

Cause:
The factory is not in the classpath.

Action:
Ensure that the factory is in the classpath.

BEA-260118
A null target was included in a deployment request.

Category:
J2EE Deployment SPI

Cause:
The target list is invalid.

Action:
Resolve the client programming error.

BEA-260119
The path provided, "{0}", does not represent a directory.

Category:
J2EE Deployment SPI

Cause:
The first argument must be a directory.

Action:
Resolve the client programming error.

BEA-260121
Initiating {0} operation for application, {1} [archive: {2}], to {3}.

Category:
J2EE Deployment SPI

Cause:
A deployment operation is starting.

Action:
No action is required.

BEA-260122
Initiating {0} operation for application, {1}, from stream to {2}.

Category:
J2EE Deployment SPI

Cause:
A deployment operation is starting.

Action:
No action is required.

BEA-260123
Unable to determine targets for deployment request on application, {0}

Category:
J2EE Deployment SPI

Cause:
No targets were specified for the new deployment.

Action:
Specify the targets to which you want to deploy the application.

BEA-260124
configured targets

Category:
J2EE Deployment SPI

Cause:
No targets were specified.

Action:
No action is required.

BEA-260125
Errors were detected when attempting to communicate with Administration Server: {0}

Category:
J2EE Deployment SPI

Cause:
Depends on the specific error. The associated exception will contain the root exception.

Action:
The course of action depends on the specific error. See the exception.

BEA-260126
Cannot override plan version, "{0}", with version from options, "{1}".

Category:
J2EE Deployment SPI

Cause:
A plan version was specified in the deployment options, but the plan defines its own version.

Action:
Avoid specifying the plan version.

BEA-260128
Changes not allowed to DTD based descriptors. The attempt to modify property "{0}" in {1} for module "{2}" will be vetoed if possible. The change will not be persisted in either case.

Category:
J2EE Deployment SPI

Cause:
A property in a DTD based descriptor was modified.

Action:
Upgrade the application with schema based descriptors.

BEA-260129
Export not allowed on DTD based descriptors. No properties for the {0} descriptor in module, "{1}", will be exported.

Category:
J2EE Deployment SPI

Cause:
An attempt was made to export a DTD based descriptor.

Action:
Upgrade the application with schema based descriptors.

BEA-260130
Shutting down Deployment Manager connection failed.

Category:
J2EE Deployment SPI

Cause:
See the message detail.

Action:
Allocate a new Deployment Manager.

BEA-260131
No URI was provided.

Category:
J2EE Deployment SPI

Cause:
An attempt was made to create a Deployment Manager without providing an appropriate deployer URI.

Action:
Provide an appropriate deployer URI.

BEA-260132
"{0}" is not a child of "{1}".

Category:
J2EE Deployment SPI

Cause:
"{0}" is not a child of "{1}".

Action:
Check for a preceding conflict start message in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-260133
The descriptor at "{0}" could not be parsed due to error: {1}.

Category:
J2EE Deployment SPI

Cause:
The named descriptor is invalid.

Action:
No action is required.

BEA-260134
Unable to identify application for {0} operation.

Category:
J2EE Deployment SPI

Cause:
Insufficient information was provided to identify which application to deploy.

Action:
Resolve the client programming error.

BEA-260137
Failures were detected while restoring the original plan file {0}. The current plan may not reflect the accurate state of the application. Either attempt to update the application again with the current plan, or make use of the backup plan "{1}".

Category:
J2EE Deployment SPI

Cause:
Failures were detected while restoring the original plan file {0}. The current plan may not reflect the accurate state of the application.

Action:
Either attempt to update the application again with the current plan or make use of the backup plan "{1}".

BEA-260138
Failures were detected while trying to create a backup plan.xml file at "{1}" {0}.

Category:
J2EE Deployment SPI

Cause:
Failures were detected while trying to create a backup plan.xml file at "{1}" {0}.

Action:
Failures were detected while trying to create a backup plan.xml file at "{1}" {0}.

BEA-260139
Unchanged plan.xml was restored due to problems updating new plan {0}.

Category:
J2EE Deployment SPI

Cause:
Unchanged plan.xml was restored due to problems updating new plan {0}.

Action:
Unchanged plan.xml was restored due to problems updating new plan {0}.

BEA-260140
Unable to remove descriptor bean {0} due to "{1}". The remover should first check to see if the bean is removable in the deployment plan prior to removing it.

Category:
J2EE Deployment SPI

Cause:
Unable to remove descriptor bean {0} due to {1}.

Action:
The remover should first check to see if the bean is removable in the deployment plan prior to removing it.

BEA-260141
An attempt to reinitialize this object by calling either inspect() or initializeConfiguration() was made without first calling close(). This SessionHelper object is stateful and must be properly closed by calling close().

Category:
J2EE Deployment SPI

Cause:
An attempt to reinitialize this object by calling either inspect() or initializeConfiguration() was made without first calling close(). This SessionHelper object is stateful and must be properly closed by calling close().

Action:
Call close() on the SessionHelper instance, and avoid reusing the same instance.

BEA-260142
The descriptor at "{0}" in module "{1}" is not recognized, and could not be parsed.

Category:
J2EE Deployment SPI

Cause:
The descriptor was not recognized and could not be parsed.

Action:
No action is required.

BEA-260143
"{0}" and "{1}" cannot both be specified.

Category:
J2EE Deployment SPI

Cause:
The combination of the two parameters is inconsistent.

Action:
Use only one of the parameters.

BEA-260144
The specified partition "{0}" does not exist in the domain.

Category:
J2EE Deployment SPI

Cause:
A partition needs to exist in the domain before deploying to it.

Action:
Create the specified partition before deploying to it.

BEA-260145
The specified resource group "{0}" does not exist in the specified partition "{1}".

Category:
J2EE Deployment SPI

Cause:
A resource group needs to exist before deploying to it.

Action:
Create the specified resource group before deploying to it.

BEA-260146
The specified resource group template "{0}" does not exist in the domain.

Category:
J2EE Deployment SPI

Cause:
A resource group template needs to exist before deploying to it.

Action:
Create the specified resource group template before deploying to it.

BEA-260147
The resource group name cannot be derived in this case. Specify the resource group option along with the partition option.

Category:
J2EE Deployment SPI

Cause:
A resource group option need to be specified with the partition option for the cases where it cannot be derived.

Action:
Specify the resource group option with partition option.

BEA-260148
A resource group template option cannot be specified with a resource group option.

Category:
J2EE Deployment SPI

Cause:
Cannot specify a resource group template option and a resource group option together.

Action:
Either specify a resource group template option or specify a resource group option.

BEA-260149
The specified resource group "{0}" does not exist in the domain.

Category:
J2EE Deployment SPI

Cause:
A resource group needs to exist before deploying to it.

Action:
Create the specified resource group before deploying to it.

BEA-260150
A partition administrator cannot perform deployment operations to a resource group template.

Category:
J2EE Deployment SPI

Cause:
A partition administrator cannot operate on a resource group template.

Action:
Operate on the resource group template as a system administrator.

BEA-260151
Partition administrator from partition {0} cannot perform deployment operations to partition {1}.

Category:
J2EE Deployment SPI

Cause:
A partition administrator is trying to operate someone else' partition.

Action:
A partition administrator should only operate on their own partition.

BEA-260152
"config-root" {0} is not a directory/file.

Category:
J2EE Deployment SPI

Cause:
The "config-root" may not have been set properly.

Action:
Verify that the "config-root" is correct.

BEA-260153
"config-root"should not be empty.

Category:
J2EE Deployment SPI

Cause:
The "config-root" may not have been set properly.

Action:
Verify that the "config-root" is correct/not empty.

BEA-280008
Opening the persistent file store "{0}" for recovery: directory={1} requestedWritePolicy="{2}" fileLockingEnabled={3} driver="{4}".

Category:
Store

Cause:
Informational message.

Action:
No action required.

BEA-280009
The persistent file store "{0}" ({1}) has been opened: blockSize={2} actualWritePolicy="{3}" explicitIOEnforced={4} records={5}.

Category:
Store

Cause:
Informational message.

Action:
No action required.

BEA-280012
Recovery is not yet complete.

Category:
Store

Cause:
This was caused by a programming error.

Action:
Check the code and try again.

BEA-280013
The specified store record is longer than the maximum length of {0} bytes.

Category:
Store

Cause:
This was caused by a programming error.

Action:
Either change the code or increase the size of the record.

BEA-280019
There was an error while writing to a storage.

Category:
Store

Cause:
See the detail message for the cause.

Action:
Ensure that the hardware and operating system are functioning properly and that there is enough space available for the storage area.

BEA-280020
There was an error while reading from the storage.

Category:
Store

Cause:
See the detail message for the cause.

Action:
Ensure that the hardware and operating system are functioning properly and that all the storage spaces are available online.

BEA-280021
There was an error while opening the file store file "{0}".

Category:
Store

Cause:
Either the specified file does not exist, the server does not have permissions to open the file, or there is a hardware or operating system problem.

Action:
Ensure that the file exists and that the directory name was specified correctly.

BEA-280024
There was an error while creating a new file named "{0}" for the file store.

Category:
Store

Cause:
See the detail message. The disk may be full, or there may be a hardware or operating system problem.

Action:
Ensure that there is enough disk space and that the hardware and operating system are working properly.

BEA-280026
The primary or cache file "{0}" is not both readable and writeable.

Category:
Store

Cause:
The file permissions are incorrect, or the server is running under the wrong user ID.

Action:
Fix the file permissions or run the server under the correct user ID.

BEA-280029
The store record {0} could not be found.

Category:
Store

Cause:
This is caused by a programming error.

Action:
Ensure that the correct record ID was specified.

BEA-280031
The store named "{0}" has not yet been opened.

Category:
Store

Cause:
This is a programming error.

Action:
Fix the code and try again.

BEA-280032
The store suffered a fatal error and it must be reopened.

Category:
Store

Cause:
A fatal error occurred previously.

Action:
Restart the server.

BEA-280035
Unable to access the store directory "{0}".

Category:
Store

Cause:
See the detail message.

Action:
Check that the specified path name is correct, that it exists, and that the directory is readable and writeable by the server's user ID.

BEA-280036
Missing the file store file "{0}" in the directory "{1}".

Category:
Store

Cause:
The file has been accidentially deleted or moved, or the wrong directory name was specified, or the server process does not have permissions to read and write the file.

Action:
Ensure that the directory name is correct and that the server process has permissions to read and write the files. If necessary, create an empty file with the same name.

BEA-280037
The file store has reached the maximum number of {0} files and no more files can be created.

Category:
Store

Cause:
There are too many records in the store.

Action:
Delete data from the store and try again.

BEA-280038
An error occurred while flushing the contents of a file store file.

Category:
Store

Cause:
See the detail message.

Action:
See the detail message.

BEA-280039
The store handle {0} is not valid.

Category:
Store

Cause:
This is caused by a programming error.

Action:
Fix the code and try again.

BEA-280040
An invalid record was found in the store: Code={0}.

Category:
Store

Cause:
The store has been corrupted, possibly by a hardware or operating system error.

Action:
For File store, Change the DirectIOMode or restore from backup if the problem persists.

BEA-280041
A record was found in the store with an invalid version of {0}

Category:
Store

Cause:
The store may have been used with an incompatible version of WebLogic Server.

Action:
Restore from backup.

BEA-280042
The file store primary or cache file "{0}" cannot be opened because it is actually a directory.

Category:
Store

Cause:
A directory was accidentially created in the file store's own main or cache directory, or the specified path is incorrect.

Action:
Check that the file store path is correct.

BEA-280044
The file store directory "{0}" does not exist.

Category:
Store

Cause:
The directory has not yet been created, or its filesystem is not available.

Action:
Check that the directory path has been correctly specified, and create the directory if necessary.

BEA-280045
The file store primary or cache directory "{0}" is not a directory.

Category:
Store

Cause:
The directory has not yet been created, or its filesystem is not available.

Action:
Check that the directory path has been correctly specified, remove any file or directory that already exists in its place, and create the directory if necessary.

BEA-280046
The directory "{0}" is not both readable and writeable.

Category:
Store

Cause:
The file permissions are incorrect, or the server is running under the wrong user ID.

Action:
Fix the file permissions or run the server under the correct user ID.

BEA-280051
The store was not able to create a new record.

Category:
Store

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-280052
The store was not able to read a record.

Category:
Store

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-280055
Invalid name for store write policy: "{0}".

Category:
Store

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-280056
A store error occurred: {0}

Category:
Store

Cause:
See the description of the underlying exception.

Action:
See the description of the underlying exception

BEA-280057
The store named "{0}" is already open.

Category:
Store

Cause:
This is a programming error.

Action:
Fix the code and try again.

BEA-280059
"{0}" is not a valid store connection name.

Category:
Store

Cause:
This is a programming error.

Action:
Fix the code and try again.

BEA-280060
The store "{0}" encountered a fatal error, and it must be shut down: {1}

Category:
Store

Cause:
There was a serious I/O error, either with file I/O, replicated store IO or the JDBC connection to the database.

Action:
Restart the server.

BEA-280061
The store "{0}" could not be deployed: {1}

Category:
Store

Cause:
See he detail message.

Action:
See the detail message.

BEA-280062
The store "{0}" could not be shut down: {1}

Category:
Store

Cause:
See the detail message.

Action:
See the detail message.

BEA-280063
The "{0}" field value "{1}" in table reference "{2}" (format [[[catalog.]schema.]table) is too long. The database supports a maximum length of "{3}" for this field.

Category:
Store

Cause:
This is a configuration error.

Action:
When configuring a table name, choose a shorter name for the indicated field. Note that JDBC stores automatically append "WLStore" to the table name.

BEA-280064
{0} (server="{1}" store="{2}" table="{3}")

Category:
Store

Cause:
See the exception text, and linked exception (if one exists).

Action:
See the exception text, and linked exception (if one exists).

BEA-280065
{0} (server="{1}" store="{2}" table="{3}"):(Linked Cause, "{4}")

Category:
Store

Cause:
See the exception text and linked exception text.

Action:
See the exception text and linked exception text.

BEA-280066
Empty field value in table reference "{0}" (format [[[catalog.]schema.]table).

Category:
Store

Cause:
This is a configuration error.

Action:
Ensure that the entire table reference is blank, or that the table field is not blank. If there is no schema, make sure there are no periods "." in the table reference. Do not start the table reference with a period ".". Note that JDBC stores automatically append "WLStore" to table references.

BEA-280067
JDBC store "{0}" did not find a database table at "{1}", so it created one using the commands in file "{2}".

Category:
Store

Cause:
The JDBC store did not find its backing table, so it created one.

Action:
No action is required.

BEA-280068
JDBC store failed to initialize. It did not find its database table and failed trying to create a new empty table using the commands in file "{0}".

Category:
Store

Cause:
See the linked exception text and linked exception stack trace.

Action:
See the linked exception text and linked exception stack trace.

BEA-280069
JDBC store failed to initialize. It did not find an already existing database table and failed to create a new empty table because the JDBC driver is unknown and/or unsupported. To force table creation with an unknown and/or unsupported driver, see the JDBC store "CreateTableDDLFile" configuration attribute. Driver information: database product name = "{0}", driver name = "{1}".

Category:
Store

Cause:
See the exception text and exception stack trace.

Action:
See the text exception text and exception stack trace.

BEA-280070
JDBC store failed to initialize. It did not find an already existing database table and failed to create a new empty table because it could not locate the configured DDL file "{0}".

Category:
Store

Cause:
The configured file is located in the server file path.

Action:
For supported databases, consider the option of not configuring a custom DDL file. There is usually no need to configure a custom DDL file unless custom database-specific tuning commands have been added to the file. If a DDL file must be configured (perhaps because it is for an unsupported database), ensure that the configured file is located either in the server file path or server class path.

BEA-280071
JDBC store "{0}" opened table "{1}" and loaded {2,choice,0#0 records|1#1 record|2#{0} records}. For additional JDBC store information, use the diagnostics framework while the JDBC store is open.

Category:
Store

Cause:
A JDBC store booted.

Action:
No action is required.

BEA-280072
JDBC store "{0}" failed to open table "{1}".

Category:
Store

Cause:
See the linked exception.

Action:
See the linked exception.

BEA-280073
The file store "{0}" could not be opened because it contained a file with an invalid version {1}. A file of version {2} was expected.

Category:
Store

Cause:
The file store has not been properly upgraded from a previous version of WebLogic Server, or the file has been corrupted on the disk.

Action:
Ensure that the file store was upgraded using the weblogic.Upgrade tool.

BEA-280074
The store "{0}" encountered an unresolvable failure while processing transaction "{1}". Shut down and restart to resolve this transaction. {2}

Category:
Store

Cause:
There was a serious I/O error, either with file I/O, replicated I/O or the JDBC connection to the database, or an unexpected exception occurred while processing a transaction.

Action:
Restart the server.

BEA-280075
JDBC store "{0}" failed to retain ownership of database table "{1}", either due to database access problems or due to concurrent accessors of the table. See the linked exception for more information.

Category:
Store

Cause:
Some other WebLogic server process or JDBC store has taken over ownership of the database table, or some database access error prevented this JDBC store from renewing ownership of the database table.

Action:
The error message has information to identify potential owners in conflict.

BEA-280076
Database table "{1}" for store "{0}" is currently owned by "{2}". Trying to wait for ownership.

Category:
Store

Cause:
Some other WebLogic Server process or JDBC store has ownership of the database table.

Action:
The warning message has information to identify the current owner of the database table. If the current owner does not yield ownership within some time, this server will not be able to open the JDBC store and will log an error.

BEA-280077
JDBC store "{0}" in this server is not the owner of database table "{1}". Unexpected current owner is "{2}", expected current owner is "{3}".

Category:
Store

Cause:
Some other WebLogic Server process or JDBC store has ownership of the database table.

Action:
The error message has information to identify and resolve the owners in conflict.

BEA-280078
The handle that was passed was created from a different store connection.

Category:
Store

Cause:
This is a programming error.

Action:
Ensure that the correct connection was used.

BEA-280079
An instance of the mSA PersistentStore

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280080
Number of create requests issued by this store.

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280081
Number of read requests issued by this store.

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280082
Number of update requests issued by this store

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280083
Number of delete requests issued by this store

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280084
Number of objects contained in the store

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280085
Number of times the store flushed its data to durable storage

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280086
An instance of an mSA PersistentStoreConnection

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280087
Number of create requests issued by this store connection

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280088
Number of read requests issued by this store connection

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280089
Number of update requests issued by this store connection

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280090
Number of delete requests issued by this store connection

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280091
Number of objects contained in the store connection

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280092
Specified value "{1}" of the property "{0}" is not a valid Integer system property. Using default value "{2}" instead.

Category:
Store

Cause:
See the message body.

Action:
Check the Javadoc for the valid formats of Integer system properties: http://java.sun.com/j2se/1.5.0/docs/api/java/lang/Integer.html#decode(java.lang.String).

BEA-280093
Block size "{1}" specified by the property {0} is outside the valid range from {2} to {3}. Using default value "{2}" instead.

Category:
Store

Cause:
See the message body.

Action:
Refer to the JMS chapter of the Performance and Tuning for Oracle WebLogic Server guide for details of this setting.

BEA-280094
The size "{1}" specified by the property {0} is not power of 2. Rounding down to "{2}" instead.

Category:
Store

Cause:
See the message body.

Action:
Refer to the JMS chapter of the Performance and Tuning for Oracle WebLogic Server guide for details of this setting.

BEA-280095
Opening existing file store "{1}". The block size value specified by the property {0} is ignored because the block size of preexisting files cannot change.

Category:
Store

Cause:
See the message body.

Action:
Refer to the JMS chapter of the Performance and Tuning for Oracle WebLogic Server guide for details of this setting.

BEA-280096
Opening existing store "{2}". The direct IO mode "{1}" specified by the property "{0}" is invalid and will be ignored. Using the default value "{3}"

Category:
Store

Cause:
See the message body.

Action:
Use a valid direct I/O mode. The valid values are: "read-buffered", "single-handle-unbuffered", and "single-handle-buffered".

BEA-280097
A file store failed to open file "{0}" in the Direct-Write read-buffered/write-unbuffered mode and is instead opening the file in a purely unbuffered mode. When there are high request loads, this may reduce file store performance. However, the store is still operating in a transactionally safe synchronous mode.

Category:
Store

Cause:
See the message body.

Action:
To fix this problem, configure a different synchronous write policy, or if using the Direct-Write policy, force the store into read-write-buffered mode using the AvoidDirectIO command line property documented in the store chapter of the Performance and Tuning Guide.

BEA-280101
The persistent file store "{0}" is forced to use buffered I/O because the Operating System or hardware environment does not support unbuffered I/O. The store is still operating in a transactionally safe synchronous mode. See store open log messages for the final write policy.

Category:
Store

Cause:
See the message body.

Action:
See the documentation for store synchronous write policy configuration.

BEA-280102
The perisistent file store "{0}" must reinitialize its cache: recovery may take longer than usual. The signature in the cache file "{2}" for the persistent store file "{1}" could not be verified, or the cache file is missing. Ignore this Warning if this is the first time the store has ever booted. Possible causes include: first boot of store (potentially after using a write policy different from Direct-Write-With-Cache), store migration, unclean shutdown, off-line store compression, and manual removal of cache files.

Category:
Store

Cause:
The cache file is missing, or the signature stored in the cache file does not match the signature of the primary file.

Action:
Make sure that the configuration is correct, do not delete cache files, and ensure a clean shutdown.

BEA-280103
The persistent file store "{0}" will cache in {1}.

Category:
Store

Cause:
This is an informational message.

Action:
No action is required.

BEA-280104
The persistent file store "{0}" will use buffered writes instead of direct IO because the configured block size "{2}" is not a multiple of the environment"s direct IO alignment "{1}". When there are high request loads, this may reduce file store performance. The store is still operating in a transactionally safe synchronous mode.

Category:
Store

Cause:
Direct I/O requires the block size to be a multiple of directIO granularity.

Action:
Reconfigure the store with a block size that is a multiple of the direct I/O alignment for your environment. If the store is not empty and contains useful data, use the store admin compact utility to change block size, otherwise make sure that all storage areas are removed before starting WebLogic Server again.

BEA-280105
The persistent file store "{0}" cannot open file {1}.

Category:
Store

Cause:
An IOException occurred.

Action:
No action is required.

BEA-280106
The persistent file store "{0}" cannot memory-map the locked file "{1}" and has to downgrade to explicit buffered IO. For example, in some NFS environments memory-mapping and locking are not compatible. Consider configuring a local cache directory.

Category:
Store

Cause:
See the message body.

Action:
Consult your storage vendor and operating system documentation.

BEA-280107
The store record {0}, connection "{1}", in the store named "{2}" does not exist because it has been deleted.

Category:
Store

Cause:
This was caused by a programming error.

Action:
Ensure that the correct record ID was specified.

BEA-280108
The store record {0}, connection "{1}" already exists in the store named "{2}".

Category:
Store

Cause:
This was caused by a programming error.

Action:
Ensure that the correct record ID was specified.

BEA-280109
The JVM was unable to load the native wlfileio library for the store "{0}". File and paging stores will continue to function correctly. Specifically, file stores that are configured with a transactionally safe synchronous write policy will continue to operate safely and transactionally but may open with a different write-policy. Other store types may not be able to open.

Category:
Store

Cause:
See message body.

Action:
See file store open log messages for the requested and final file store write policies. See the documentation for file store synchronous write policy configuration.

BEA-280110
The "{1}" attribute of Store "{0}" has been changed from "{2}" to "{3}".

Category:
Store

Cause:
This is due to a configuration change.

Action:
No action is required.

BEA-280111
The "{1}" attribute of Store "{0}" has been changed from "{2}" to "{3}".

Category:
Store

Cause:
This is due to a configuration change.

Action:
No action is required.

BEA-280112
[StoreBootOnError] "{0}" Ignoring AssertionError on bootHandle: record type: {1}, handle:{2}, row: {3}

Category:
Store

Cause:
There is some corruption of the JDBC store.

Action:
Contact My Oracle Support.

BEA-280113
The JDBC store "{0}" is initially pointing to RAC instance "{1}".

Category:
Store

Cause:
See the message body.

Action:
No action required.

BEA-280114
The JDBC store "{0}" is configured with worker count as "{1}" but only started "{2}" workers as it is not able to acquire enough JDBC connections for the configured worker count.

Category:
Store

Cause:
The JDBC store was not able to acquire enough JDBC connections for the configured worker count.

Action:
Modify the data source configuration.

BEA-280115
Replicated store "{0}": the daemon is approaching its shared memory limit and the store itself has used up to "{1}%" of its shared memory.

Category:
Store

Cause:
See the message body.

Action:
No action is required.

BEA-280116
Replicated store "{0}": the daemon is approaching its shared memory limit and the store itself has used up to "{1}%" of its shared memory. It will reject new JMS persistent messages.

Category:
Store

Cause:
See the message body.

Action:
Check if there are things that need to be cleaned up, for example abandoned durable subscriptions. Consider restart the daemon with a bigger limit.

BEA-280117
Replicated store "{0}" the daemon has used up to "{1}%" of its shared memory limit.

Category:
Store

Cause:
This is an informational message.

Action:
No action is required.

BEA-280118
Replicated store "{0}": the daemon has used up to "{1}%" of its shared memory limit. It may take actions, including rejecting new JMS persistent messages or failing on creating any new stores or opening any recovered stores.

Category:
Store

Cause:
The amount of shared memory used by the replicated store daemon has met or exceeded the configured warning threshold.

Action:
Check if there are things that need to be cleaned up, for example abandoned durable subscriptions. Consider restart the daemon with a bigger limit.

BEA-280119
Replicated store "{0}": the daemon used up to "{1}%" of its shared memory limit. It will fail on creating new stores or opening any recovered store.

Category:
Store

Cause:
The amount of shared memory used by the replicated store daemon has met or exceeded the configured error threshold.

Action:
Check if there are things that need to be cleaned up, for example abandoned durable subscriptions. Consider restart the daemon with a bigger limit.

BEA-280120
Opening the Replicated store "{0}(Region Name={1})" for recovery: directory={2} driver="{3}".

Category:
Store

Cause:
Informational message.

Action:
No action required.

BEA-280121
The Replicated store "{0}(Region Name={1})" ({2}) has been opened: blockSize={3} records={4}.

Category:
Store

Cause:
Informational message.

Action:
No action required.

BEA-280122
Missing the region "{1}" from this replicated store(name="{0}").

Category:
Store

Cause:
The region has been accidentially deleted or moved, or the wrong name was specified, or the server process does not have permissions to read and write to the region.

Action:
Ensure that the replicated Store name is correct and that the server process has permissions to read and write to the regions in replicated store. If necessary, create an empty region with the same name.

BEA-280123
The replicated store has reached the maximum number of {0} regions and no more region can be created.

Category:
Store

Cause:
There are too many records in the store.

Action:
Delete data from the store and try again.

BEA-280124
An error occurred while flushing the contents of a replicated store region.

Category:
Store

Cause:
See the detail message.

Action:
See the detail message.

BEA-280125
The replicated store "{0}(Region Name={1})" could not be opened because it contained a region with an invalid version {2}. A region of version {3} was expected.

Category:
Store

Cause:
The replicated store has not been properly upgraded from a previous version of WebLogic Server, or the region has been corrupted on the memory store.

Action:
Ensure that the file store was upgraded using the weblogic.Upgrade tool.

BEA-280126
Opening existing replicated store "{1}(Region Name={2})". The block size value specified by the property {0} is ignored because the block size of preexisting regions cannot change.

Category:
Store

Cause:
See the message body.

Action:
Refer to the JMS chapter of the Performance and Tuning for Oracle WebLogic Server guide for details of this setting.

BEA-280127
The replicated store "{0}" cannot open region {1}.

Category:
Store

Cause:
An IOException occurred.

Action:
No action is required.

BEA-280128
The store can't be initialized.

Category:
Store

Cause:
See the message body.

Action:
Please check that the cryptographic services of the execution environment and the host operating system are properly configured and operating correctly.

BEA-280129
JDBC store "{0}" will be opened with connection caching policy "{1}" and will keep {2,choice,1#1 database connection|2#{2} database connections} open.

Category:
Store

Cause:
Informational message.

Action:
No action is required.

BEA-280130
The configuration property "{2}" with value "{3}" on JDBC store "{0}" is incompatible with connection policy "{1}".

Category:
Store

Cause:
Conflicting configuration options.

Action:
Either the connection caching policy must be changed or the property value must be changed.

BEA-280131
The use of piggy-back commit is incompatible connection policy "{1}" and has been disabled for JDBC store "{0}".

Category:
Store

Cause:
Conflicting configuration options.

Action:
Either the connection caching policy must be changed or the property value must be changed.

BEA-280132
JDBC store "{0}" will be opened with connection caching policy "{1}" and will get one connection from its data source as needed.

Category:
Store

Cause:
Informational message.

Action:
No action is required.

BEA-280133
The version record is missing from the table "{1}" for the JDBC store "{0}". Make sure that only Weblogic processes are accessing and modifying the table.

Category:
Store

Cause:
The version record is missing from the non-empty table backing the JDBC store.

Action:
Contact My Oracle Support regarding restoring the version record in the JDBC store.

BEA-280134
The version record is missing from the table "{1}" for the JDBC store "{0}" and will be restored.

Category:
Store

Cause:
Informational message.

Action:
No action is required.

BEA-280135
The non-critical store "{0}" failed to open and some associated features may be impacted. Please consult the log for more details.

Category:
Store

Cause:
See the log files.

Action:
See the detail message.

BEA-280136
DEPRECATION NOTICE: With WebLogic Server 12.2.1.3 and with the Exalogic X6 initial release, the WebLogic Replicated Store for JMS messages is deprecated. It will be removed in a future release. Oracle recommends that you use either a custom file store or a JDBC store for JMS message storage. See "Administering the WebLogic Persistent Store" in the documentation for more information about these options.

Category:
Store

Cause:
A deprecated store type is in use.

Action:
Oracle recommends using a file store or a JDBC store.

BEA-281002
The SAF service has been started.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281003
The SAF service has been initialized.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281004
The SAF service has been suspended.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281005
The SAF service has been shut down.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281006
FailedMessage for store-and-forward: MessageId={0} > </FailedMessage.

Category:
SAFService

Cause:
A message expired before it was successfully forwarded by an SAF agent, and there is no error handling policy configured for the endpoint. The message ID was logged.

Action:
No action is required.

BEA-281007
SAF Agent "{0}" has been successfully prepared.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281008
SAF Agent "{0}" has been successfully activated.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281009
SAF Agent "{0}" has been deactivated.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281010
SAF Agent "{0}" has been unprepared.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281011
SAF Agent "{0}" failed to be prepared because of exception "{1}".

Category:
SAFService

Cause:
There was either an error in the configuration.

Action:
Check the agent's configuration.

BEA-281012
SAF Agent "{0}" failed to be started because of exception "{1}".

Category:
SAFService

Cause:
There was either an error in the configuration.

Action:
Check the agent's configuration.

BEA-281016
SAFAgent "{0}" byte threshold for the agent has been exceeded.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281017
SAFAgent "{0}" byte threshold for agent has cleared.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281018
SAFAgent "{0}" message threshold for the agent has been exceeded.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281019
SAFAgent "{0}" message threshold for the agent has cleared.

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281020
SAF service has successfully connected to the remote endpoint "{0}".

Category:
SAFService

Cause:
This is an informational message.

Action:
No action is required.

BEA-281021
SAF service failed to connect to the remote endpoint "{0}", because of {1}.

Category:
SAFService

Cause:
This is either due to a configuration error or a network failure, or the remote endpoint is temporarily unavailable.

Action:
Check the configuration, the network connection, or the remote endpoint.

BEA-281022
SAF Agent "{0}" failed to resume because of exception "{1}".

Category:
SAFService

Cause:
There was either an error in the configuration.

Action:
Check the agent's configuration.

BEA-281025
SAFAgent "{0}" has been paused for incoming messages.

Category:
SAFService

Cause:
An Incoming Message Pause request was issued for the specified SAFAgent.

Action:
No action is required.

BEA-281026
SAFAgent "{0}" has been resumed for new incoming messages.

Category:
SAFService

Cause:
An Incoming Message Resume request was issued for the specified SAFAgent.

Action:
No action is required.

BEA-281027
SAFAgent "{0}" has been paused for forwarding

Category:
SAFService

Cause:
A Forwarding Pause request was issued for the specified SAFAgent.

Action:
No action is required.

BEA-281028
SAFAgent "{0}" has been resumed for forwarding.

Category:
SAFService

Cause:
A Forwarding Resume request was issued for the specified SAFAgent.

Action:
No action is required.

BEA-281029
RemoteEndpoint "{0}" has been paused for new incoming messages.

Category:
SAFService

Cause:
An Incoming Pause Request was issued for the specified remote endpoint.

Action:
No action is required.

BEA-281030
RemoteEndpoint "{0}" has been resumed for new incoming messages.

Category:
SAFService

Cause:
An Incoming Resume Request was issued for the specified remote endpoint.

Action:
No action is required.

BEA-281031
RemoteEndpoint "{0}" has been paused for forwarding.

Category:
SAFService

Cause:
A Forwarding Pause Request was issued for the specified remote endpoint.

Action:
No action is required.

BEA-281032
RemoteEndpoint "{0}" has been resumed for forwarding.

Category:
SAFService

Cause:
A Forwarding Resume request was issued for the specified remote endpoint.

Action:
No action is required.

BEA-282000
Unsupported class version {0}. Expected a value between {1} and {2} inclusive.

Category:
Messaging

Cause:
While attempting to interoperate between different releases or service packs, an error occurred while attempting to serialize or deserialize an object. The version number of the object was not in the expected range. If {0} is larger than {2}, then it is possible an attempt was made to access a newer version than the current version. Otherwise, a possible attempt has been made to interoperate with an unsupported older version.

Action:
Ensure that the versions of Oracle products that are interoperating are supported. If the versions need to be supported, contact My Oracle Support.

BEA-282001
The messaging kernel {0} is beginning recovery of its persistent state.

Category:
Messaging

Cause:
This is normal operation.

Action:
No action is required.

BEA-282002
The messaging kernel {0} has recovered {1} persistent messages.

Category:
Messaging

Cause:
This is normal operation.

Action:
No action is required.

BEA-282003
The messaging kernel {0} will use up to {1} bytes of memory before paging begins.

Category:
Messaging

Cause:
This is normal operation.

Action:
No action is required.

BEA-282004
Message redirection has failed in a non-recoverable way for the messaging kernel {0}. Restart the server in order to restart message redirection.

Category:
Messaging

Cause:
See the previous error messages, which should explain the cause.

Action:
Restart the WebLogic Server.

BEA-282005
An error occurred while redirecting a message for the messaging kernel {0}: {1}.

Category:
Messaging

Cause:
See the attached detail message.

Action:
No action is required.

BEA-282006
An error occurred while deleting an expired message for the messaging kernel {0}: {1}.

Category:
Messaging

Cause:
See the attached detail message.

Action:
No action is required.

BEA-282007
An error occurred in the transaction prepare phase of a message send operation for the messaging kernel {0}.

Category:
Messaging

Cause:
See the attached stack trace.

Action:
No action is required.

BEA-282008
A message send transaction for the messaging kernel {0} could not be committed because the kernel has been shut down.

Category:
Messaging

Cause:
A server was shut down or a destination was removed while a transaction was in progress.

Action:
No action is required.

BEA-282009
A message receive transaction for the messaging kernel {0} could not be committed because the kernel has been shut down.

Category:
Messaging

Cause:
A server was shut down or a destination was removed while a transaction was in progress.

Action:
No action is required.

BEA-282010
A sequence number update transaction for the messaging kernel {0} could not be committed because the kernel has been shut down.

Category:
Messaging

Cause:
A server was shut down or a destination was removed while a transaction was in progress.

Action:
No action is required.

BEA-282011
There was an error making a message visible after a delivery delay: {0}.

Category:
Messaging

Cause:
Most likely, a transient I/O error occurred.

Action:
Consider restarting the server if the error persists. The message will not be lost.

BEA-282012
There was a failure while performing paging I/O.

Category:
Messaging

Cause:
Either a transient I/O error occurred, or the server did not have enough memory to complete the paging I/O request.

Action:
Consider restarting the server if the error persists.

BEA-282013
Skipping unexpected null message encountered on store boot, {0}.

Category:
Messaging

Cause:
Message data corruption has occurred. The corrupted message will be skipped to allow data recovery on other non-corrupted messages.

Action:
Report this issue to My Oracle Support.

BEA-282014
[StoreBootOnError] "{0}" Ignoring 2PC record for sequence={1}, queue={2}, type={3}, id={4}, xid={5}; message reference element cannot be found.

Category:
Messaging

Cause:
Potential message data corruption has occurred. A 2PC record was found in the store without an associated message reference element. The 2PC record will be ignored.

Action:
Contact My Oracle Support.

BEA-282015
"{0}" An error occurred while writing a message to store: info={1}; null message body detected.

Category:
Messaging

Cause:
An error was detected while attempting to write a message to the persistent store.

Action:
Contact My Oracle Support.

BEA-282016
A problem occurred while SAF Agent "{0}" recovered SAF messages from its persistent store: data was found in both old (pre-12.2.1.0.0) store connections and in new (12.2.1.x.0) store connections. The old store connections and the data within them are going to be ignored.

Category:
Messaging

Cause:
The SAF agent in question has been upgraded from a pre-12.2.1.0.0 release to an unpatched 12.2.1.x.0 release while it had unprocessed persistent messages, and then upgraded to a patched 12.2.1.x.0 release. As a result, there are pre-12.2.1.0.0 data (which were ignored during the first upgrade), and unpatched 12.2.1.x.0 data in the store.

Action:
Use -Dweblogic.saf.StoreUpgradeMode="OldOnly" to recover only the old messages. Use -Dweblogic.saf.StoreUpgradeMode="IgnoreOld" to suppress this warning message. Or contact My Oracle Support.

BEA-283002
Path Service has been started on server {0} with jndiName {1} with store {2}

Category:
PathService

Cause:
See the message body.

Action:
No action required.

BEA-290001
Error occurred in the deployment service servlet. It received an unacceptable request of type "{0}" with content type "{1}".

Category:
DeploymentService

Cause:
An invalid request was made to the deployment service servlet.

Action:
This is an internal WebLogic Server error. No action is required. If the problem persists, contact My Oracle Support.

BEA-290003
Deployment service servlet encountered an exception while handling request of type "{0}". Exception is: "{1}".

Category:
DeploymentService

Cause:
Error occurred while handling the deployment servlet request.

Action:
This is an internal WebLogic Server error. Refer to the exception message and determine if the exception can be corrected. If the problem persists, contact My Oracle Support.

BEA-290006
Deployment service servlet received a request of type "{0}" with no application name.

Category:
DeploymentService

Cause:
An invalid deployment service servlet request was made.

Action:
This is an internal WebLogic Server error. No action is required. If the problem persists, contact My Oracle Support.

BEA-290007
Deployment service servlet unable to find upload directory while handling request of type "{0}" for application "{1}".

Category:
DeploymentService

Cause:
The servlet was unable to find the upload directory.

Action:
This is an internal WebLogic Server error. No action is required. If the problem persists, contact My Oracle Support.

BEA-290008
Deployment service servlet encountered an error while extracting uploaded file to directory "{0}". Exception is: "{1}".

Category:
DeploymentService

Cause:
An exception occurred while extracting the uploaded file.

Action:
This is an internal WebLogic Server error. Refer to the exception message and determine if the exception can be corrected. If the problem persists, contact My Oracle Support.

BEA-290009
Deployment service servlet failed to get initialized due to unavailable security service.

Category:
DeploymentService

Cause:
The WebLogic Server security service is not present in the installation files.

Action:
This is an internal WebLogic Server error. No action is required. If the problem persists, contact My Oracle Support.

BEA-290010
Deployment service servlet failed to get initialized due to privileged action violation. Exception is: "{0}".

Category:
DeploymentService

Cause:
An exception occurred while initializing the deployment service servlet.

Action:
This is an internal WebLogic Server error. Refer to the exception message and determine if the exception can be corrected. If the problem persists, contact My Oracle Support.

BEA-290011
Unauthorized request of type "{0}" for user "{1}"

Category:
DeploymentService

Cause:
The user is unauthorized for downloading files.

Action:
Check the user and try again with an authorized user.

BEA-290012
Deployment service servlet received jspRefresh request with no upload file name.

Category:
DeploymentService

Cause:
The request parameter upload file name was null.

Action:
This is an internal WebLogic Server error. No action is required. If the problem persists, contact My Oracle Support.

BEA-290013
No user name or password provided for the request.

Category:
DeploymentService

Cause:
The user name or password in the request were null.

Action:
This is an internal WebLogic Server error. No action is required. If the problem persists, contact My Oracle Support.

BEA-290014
Invalid user name or password.

Category:
DeploymentService

Cause:
The request contained an invalid user name or password.

Action:
Try again with a valid user name and password.

BEA-290015
Domain wide secret mismatch or clock skew between servers

Category:
DeploymentService

Cause:
Thee was an invalid signature between the Administration Server and Managed Servers.

Action:
This is an internal WebLogic Server error. Verify that the Administration Server and Managed Servers have the same SerializedSystemIni.dat file. Verify that clock skew has not occurred between the servers in the domain.

BEA-290016
Access not allowed for server "{0}" on boot.

Category:
DeploymentService

Cause:
The user does not have boot permission for the specified server.

Action:
This is an internal WebLogic Server error. No action is required. If the problem persists, contact My Oracle Support.

BEA-290020
Exceptions encountered while invoking application lifecycle listeners

Category:
DeploymentService

Cause:
A registered lifecycle listener detected an error and generated an exception.

Action:
Refer to the exception message from the lifecycle listener and determine if the error can be corrected.

BEA-290021
{0} does not exist.

Category:
DeploymentService

Cause:
The file does not exist on the Administration Server.

Action:
This is an internal WebLogic Server error. No action is required.

BEA-290022
This request needs to be initiated through a start control.

Category:
DeploymentService

Cause:
This is an internal protocol error.

Action:
This is an internal WebLogic Server error. No action is required. If the problem persists, contact My Oracle Support.

BEA-290024
Deployment type {0} has already been registered with the DeploymentService.

Category:
DeploymentService

Cause:
More than one deployment handler was registered for this deployment type.

Action:
This is an internal WebLogic Server error. No action is required. If the problem persists, contact My Oracle Support.

BEA-290025
Cannot call "start()" when DeploymentRequest has already been started.

Category:
DeploymentService

Cause:
The start method was called more than once.

Action:
This is an internal WebLogic Server error. No action is required.

BEA-290026
Request "{0}" is in "{1}" state - request has already been cancelled.

Category:
DeploymentService

Cause:
More than one cancel request was received.

Action:
No action is required.

BEA-290027
Request "{0}" is in "{1}" state - it is too late to attempt cancelling it.

Category:
DeploymentService

Cause:
A cancel request was received while the request was being committed.

Action:
No action is required.

BEA-290028
Deployment "{0}" has been cancelled.

Category:
DeploymentService

Cause:
The request was already cancelled.

Action:
No action is required.

BEA-290029
Deployment "{0}" timed out on Administration Server.

Category:
DeploymentService

Cause:
The request has timed out.

Action:
No action is required.

BEA-290030
No data handler registered for type "{0}".

Category:
DeploymentService

Cause:
A handler was not registered for the specified type.

Action:
This is an internal WebLogic Server error. No action is required.

BEA-290031
No tasks associated with this deployment request that can be cancelled.

Category:
DeploymentService

Cause:
Tasks have already completed.

Action:
No action is required.

BEA-290032
Data Transfer Handler exists for handler type: "{0}".

Category:
DeploymentService

Cause:
The handler type is already registered

Action:
This is an internal WebLogic Server error. No action is required.

BEA-290036
Deployment for request id "{0}" is deferred since target "{1}" is disconnected.

Category:
DeploymentService

Cause:
Target server "{1}" is disconnected.

Action:
No action is required. When the server reconnects, the deployment will be performed.

BEA-290039
Unrecognized callback

Category:
DeploymentService

Cause:
The callback was not a supported type.

Action:
This is an internal WebLogic Server error. No action is required. If the problem persists, contact My Oracle Support.

BEA-290040
The cancel call cannot be completed at this point because the deployment request "{0}" has already been partially committed.

Category:
DeploymentService

Cause:
A cancel was requested on a committed deployment task.

Action:
Wait until the deployment task has completed and then perform the necessary actions to restore the application to the desired state.

BEA-290041
Commit failed message received for id: "{0}" that has no request. It may be completed or cancelled. Sending commit succeeded message anyway.

Category:
DeploymentService

Cause:
No corresponding request was found for the commit failure message.

Action:
Check for a preceding conflict start message in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-290042
Received a commit message call without a corresponding request. It may have been completed or cancelled. Sending commit failed message.

Category:
DeploymentService

Cause:
No corresponding request was found for the commit message.

Action:
Check for a preceding conflict start message in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-290043
Cancel failure encountered when attempting to cancel "{0}" due to optimistic concurrency violation.

Category:
DeploymentService

Cause:
A failure occurred during the cancel of the request.

Action:
Wait until the deployment task has completed and then perform the necessary actions to restore the application to the desired state.

BEA-290044
{0} delivery

Category:
DeploymentService

Cause:
This is an informational message.

Action:
No action is required.

BEA-290045
prepare

Category:
DeploymentService

Cause:
Not applicable.

Action:
No action is required.

BEA-290046
commit

Category:
DeploymentService

Cause:
Not applicable.

Action:
No action is required.

BEA-290047
cancel

Category:
DeploymentService

Cause:
Not applicable.

Action:
No action is required.

BEA-290048
Request with id "{0}" timed out.

Category:
DeploymentService

Cause:
The request timed out.

Action:
Try increasing the deployment timeout value. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-290049
Deploy failed for id "{0}" since no targets are reachable.

Category:
DeploymentService

Cause:
No targets were reachable.

Action:
Ensure targeted servers are alive and available from the Administration Server.

BEA-290050
Failed to deliver commit message to the following targets "{0}".

Category:
DeploymentService

Cause:
An exception occurred while committing the deployment request.

Action:
Ensure that targeted servers are alive and available from the Administration Server. Check for a preceding conflict start message in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-290051
The commit message for the deployment "{0}" could not be completed because the deployment timed out.

Category:
DeploymentService

Cause:
The deployment timed out.

Action:
Try increasing the deployment timeout value. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-290052
{0} timeout

Category:
DeploymentService

Cause:
Not applicable.

Action:
No action is required.

BEA-290053
Request with id "{0}" timed out on the Administration Server.

Category:
DeploymentService

Cause:
The request timed out on the Administration Server.

Action:
Try increasing the deployment timeout value. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-290054
Deployment request "{0}" was explicitely cancelled.

Category:
DeploymentService

Cause:
Not applicable.

Action:
No action is required.

BEA-290055
Deployment request "{0}" timed out on the Administration Server during "{1}".

Category:
DeploymentService

Cause:
The deployment request timed out.

Action:
Try increasing the deployment timeout value. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-290056
indeterminate

Category:
DeploymentService

Cause:
Not applicable

Action:
No action is required.

BEA-290057
Invalid DeploymentRequest: the object returned by the DeploymentService has been modified in an incompatible way.

Category:
DeploymentService

Cause:
The deployment request is not of the expected type.

Action:
Check for a preceding conflict start message in the logs. Try to avoid the conflict by taking one of the suggested actions. If the problem persists, contact My Oracle Support and provide the stack trace for further analysis.

BEA-290058
There is no request corresponding to request ID "{0}" currently being processed. The request will be cancelled if it is received in the future.

Category:
DeploymentService

Cause:
The specified request ID is not active.

Action:
Check that your task ID is the task that you would like to cancel.

BEA-290059
Operation "{0}" is not one of the supported types when creating a Change Descriptor.

Category:
DeploymentService

Cause:
An invalid change descriptor type was specified.

Action:
This is an internal WebLogic Server error. If the problem persists, contact My Oracle Support.

BEA-290060
Duplicate registration for "{0}".

Category:
DeploymentService

Cause:
Two different deployment instances were registered for the same type.

Action:
This is an internal WebLogic Server error. If the problem persists, contact My Oracle Support.

BEA-290061
UnrecognizedTypes: "{0}", "{1}"

Category:
DeploymentService

Cause:
A deployment type is invalid.

Action:
This is an internal WebLogic Server error. If the problem persists, contact My Oracle Support.

BEA-290062
The server configuration is out of date with the domain configuration and an attempt to synchronize with the admin server failed in {0} phase. This server needs to be restarted to enable it to synchronize with the domain configuration.

Category:
DeploymentService

Cause:
The server configuration is out of date with the domain configuration and an attempt to synchronize with the admin server failed in {0} phase. This server needs to be restarted to enable it to synchronize with the domain configuration.

Action:
Restart the server and if that does not resolve the problem, contact My Oracle Support and provide the stack trace for further analysis.

BEA-290063
Commit for request "{0}" will not proceed further since its requires restart flag is set.

Category:
DeploymentService

Cause:
The changes in the deployment request require a restart.

Action:
Restart either the server or the system resource that is part of the request.

BEA-290064
Deployment service servlet encountered an exception while handling the deployment service message for request id "{0}" from server "{1}". Exception is: "{2}".

Category:
DeploymentService

Cause:
Error occurred while handling the deployment service message request.

Action:
This is an internal WebLogic Server error. Refer to the underlying error message and determine if the error can be corrected. Verify that there are no network connection issues between the administration and managed servers.

BEA-290065
Deployment service servlet encountered an Exception while handling the deployment datatransfer message for request id "{0}" from server "{1}". Exception is: "{2}".

Category:
DeploymentService

Cause:
Error occurred while handling the deployment datatransfer request.

Action:
This is an internal WebLogic Server error. Refer to the underlying error message and determine if the error can be corrected. Verify that there are no network connection issues between the administration and managed servers.

BEA-290066
Error occurred while downloading files from Administration Server for deployment request "{0}". Underlying error is: "{1}"

Category:
DeploymentService

Cause:
The connection used for the file download received an error.

Action:
Refer to the underlying error message and determine if the error can be corrected. Verify that there are no network connection issues between the administration and managed servers.

BEA-290067
Deployment request "{0}" was cancelled because servers: "{1}" were unreachable and the domain has cluster-constraints-enabled is set to true. To deploy to this cluster, either start the unreachable servers or remove the unreachable servers from the cluster, then reattempt the deployment. If this behaviour is not intended, set cluster-constraints-enabled on the domain to false and restart the Administration Server. This allows you to deploy the application only to those servers that can be reached.

Category:
DeploymentService

Cause:
Not all the servers in the cluster are running and cluster-constraints-enabled is set to true.

Action:
Start all the servers in the cluster and try deployment again, or if this behaviour is not intended, set cluster-constraints-enabled on the domain to false and restart the Administration Server.

BEA-290068
A deployment service request has been received by this Managed Server that was intended for the Administration Server. The source of the request is "{0}".

Category:
DeploymentService

Cause:
The source Managed Server was started with a URL for the Administration Server that incorrectly identified this server.

Action:
Start the source Managed Server with the correct URL for the Administration Server.

BEA-290069
Commit failed message received for id: "{0}", but exception details cannot be transported. Please look at target server log file for more details.

Category:
DeploymentService

Cause:
The send of the commit message failed.

Action:
Check the exception details in the server log and determine if the failure can be corrected.

BEA-290070
Deployment service servlet encountered an exception while parsing the multipart/form-data request:"{0}". Exception is: "{1}".

Category:
DeploymentService

Cause:
The request is not an RFC 1867-compliant multipart/form-data request.

Action:
This is an internal WebLogic Server error. No action is required.

BEA-290071
Deployment service servlet failed when parsing the request or uploading the file.

Category:
DeploymentService

Cause:
The request is not an RFC 1867-compliant multipart/form-data stream.

Action:
The request should comply with RFC 1867. Verify that the Administration Server and Managed Servers are running versions that interoperate.

BEA-290073
Deployment service servlet received a request of type "{0}" with an invalid application name: "{1}".

Category:
DeploymentService

Cause:
An invalid deployment service servlet request was made.

Action:
Correct the application name and retry the request.

BEA-290074
Deployment service servlet received file download request for file "{0}". The file may exist, but automatic download of this file is not allowed; it must be manually transferred.

Category:
DeploymentService

Cause:
The file to download is a security file or is outside of the domain root directory.

Action:
Enter a valid file name for download.

BEA-290075
Target Server encountered an error in sending "{0}" of id "{1}" with "{2}".

Category:
DeploymentService

Cause:
The deployment message cannot be delivered to the Administration Server.

Action:
This is an internal WebLogic Server error. No action is required.

BEA-290076
Total size of transferred files is "{0}" GB and it exceeded configured limit "{1}" GB.

Category:
DeploymentService

Cause:
Total size of transferred file exceeded the configured limit.

Action:
Delete unwanted files from the directory and try again

BEA-290077
Transfered files and its file size is like as follows.

Category:
DeploymentService

Cause:
Total size of transferred file exceeded the configured limit.

Action:
Delete unwanted files from the directory and try again

BEA-290078
"{0}" : "{1}" GB

Category:
DeploymentService

Cause:
Total size of transferred file exceeded the configured limit.

Action:
Delete unwanted files from the directory and try again

BEA-290079
Deployment service servlet received a request of type "{0}" with an invalid upload path: "{1}".

Category:
DeploymentService

Cause:
An invalid deployment service servlet request was made.

Action:
Correct the upload path and retry the request.

BEA-290080
Deployment service servlet received a request of type "{0}" with no upload path.

Category:
DeploymentService

Cause:
An invalid deployment service servlet request was made.

Action:
This is an internal WebLogic Server error. No action is required. If the problem persists, contact My Oracle Support.

BEA-290081
Deployment service servlet received a request of type "{0}" with an invalid partition name: "{1}".

Category:
DeploymentService

Cause:
An invalid deployment service servlet request was made.

Action:
Correct the partition name and retry the request.

BEA-290082
Deployment service servlet received a request of type "{0}" unable to overwrite existing file: "{1}".

Category:
DeploymentService

Cause:
An invalid deployment service servlet request was made.

Action:
Remove existing user file and retry the request.

BEA-290083
Deployment service servlet received a request of type "{0}" file already exists: "{1}".

Category:
DeploymentService

Cause:
An invalid deployment service servlet request was made.

Action:
Remove existing user file or set overwrite flag and retry the request.

BEA-290084
Can not create upload directory: {0}.

Category:
DeploymentService

Cause:
The upload directory cannot be created.

Action:
Check the file permission on the parent directory.

BEA-290085
The directory for upload is not a directory: {0}.

Category:
DeploymentService

Cause:
The directory for upload is not a directory.

Action:
Check the file path and permission on the directory.

BEA-290086
Upload directory is not writable: {0}.

Category:
DeploymentService

Cause:
Can not write to the upload directory.

Action:
Check the file permission on the directory.

BEA-290087
Data transfer between administration and managed server failed for resource "{0}".

Category:
DeploymentService

Cause:
The named resource was unavailable, the read failed, or communication between administration and managed server failed.

Action:
Inspect the underlying file-system error, correct the problem, and retry.

BEA-300037
The NodeManager at host {0} and port {1} seems to be down. Start the NodeManager and rerun the command.

Category:
NodeManager

Cause:
The NodeManager is not running.

Action:
Start the NodeManager and rerun the command.

BEA-300040
An I/O error occurred while writing a NodeManager status change message.

Category:
NodeManager

Cause:
Possible causes are that the standard output stream has been closed or the NodeManager stopped monitoring.

Action:
If this server requires monitoring, restart the server.

BEA-300043
NodeManager native library not found - server process ID not saved.

Category:
NodeManager

Cause:
The NodeManager native library is not in the library search path or is unavailable on this platform.

Action:
Ensure that the NodeManager native library is available and in the library search path.

BEA-300044
An I/O error occurred while writing the server PID file: "{0}".

Category:
NodeManager

Cause:
The server PID file might be write-protected.

Action:
Ensure that the server PID file is not write-protected. In addition, check to see if the parent directory exists (should have been created by the NodeManager server before starting the server).

BEA-300048
Unable to start the server {0} : {1}

Category:
NodeManager

Cause:
The most likely cause is a configuration error in the Shell/SSH/RSH NodeManager configuration.

Action:
Ensure that you can access the remote NodeManager. This may require setting up SSH permissions for the SSH-based NodeManager. In addition, ensure that the default PATH settings for the remote NodeManager are correct. See the NodeManager documentation for more information.

BEA-300049
An I/O error occurred while writing the server URL file: "{0}".

Category:
NodeManager

Cause:
The server URL file might be write-protected.

Action:
Ensure that the server URL file is not write-protected. In addition, check to see if the parent directory exists (it should have been created by the NodeManager server before starting the server).

BEA-300051
An I/O error occurred while updating the startup properties for "{0}". This probably occurred because the NodeManager is unreachable. This could mean that the servers boot.properties or startup.properties file is out of date, and the next time NodeManager attempts to automatically restart the server on a failure, it will use out of date properties. To resolve this issue, either ensure that the NodeManager is able to receive the updates and reset the properties, or restart the server.

Category:
NodeManager

Cause:
An I/O error occurred while updating the startup properties for "{0}". This probably occured because the NodeManager is unreachable.

Action:
Either ensure that the NodeManager is able to receive the updates and reset the properties, or restart the server.

BEA-300053
A migratable server was not found to contain any specified IP address in the ServerMBean or custom network channels for migration. No IPs will be passed to NodeManager and no IPs will be migrated. The server may not start without an available address, or may not be accessible throughout migration without a consistent IP. Configure an appropriate floating listen address for the server.

Category:
NodeManager

Cause:
A migratable server was not found to contain any specified IP address in the ServerMBean or custom network channels for migration. No IPs will be passed to NodeManager and no IPs will be migrated. The server may not start without an available address, or may not be accessible throughout migration without a consistent IP.

Action:
Configure an appropriate floating listen address for the server.

BEA-300054
Could not find appropriate IP for ListenAddress "{0}" specified for a migratable server. Reason: "{1}". The NodeManager may not be able to bind the specified address and the server may not start without the available address. Configure an appropriate floating listen address for the server.

Category:
NodeManager

Cause:
No appropriate IP was found for a migratable server's listen address. The NodeManager may not be able to bind the address specified and the server may not start without the available address. Configure an appropriate floating listen address for the server.

Action:
Configure an appropriate floating listen address for the server.

BEA-300055
The NodeManagerMonitor add requires a non-null MachineMBean to monitor the active status of a NodeManager.

Category:
NodeManager

Cause:
See the message body.

Action:
Provide a non-null MachineMBean.

BEA-300056
Could not execute the native output file rotation logic due to "{0}".

Category:
NodeManager

Cause:
Could not execute the native output file rotation logic due to "{0}".

Action:
Could not execute the native output file rotation logic due to "{0}".

BEA-300057
Starting server {0} on machine {2} at {1}

Category:
NodeManager

Cause:
Starting server {0} on machine {2} at {1}

Action:
No action is required.

BEA-300058
Starting server {0} on machine at {1}

Category:
NodeManager

Cause:
Starting server {0} on machine at {1}

Action:
No action is required.

BEA-310001
Subsystem {0} in partition {1} has failed. Setting server state to FAILED.

Category:
Health

Cause:
One of the critical subsystems of the server has failed.

Action:
Check the server log to determine the cause of the subsystem failure.

BEA-310002
{0}% of the total memory in the server is free.

Category:
Health

Cause:
The percentage of free memory in the server has changed.

Action:
No action is required.

BEA-310003
Free memory in the server is {0} bytes. There is danger of receiving an OutOfMemoryError.

Category:
Health

Cause:
Free memory in the server is very low.

Action:
Analyze heap memory usage for possible memory leak. If no memory leak is found, consider restarting server with a larger maximum heap size.

BEA-310006
Critical subsystem {0} in partition {1} has failed. Setting server state to FAILED. Reason: {2}

Category:
Health

Cause:
One of the critical subsystems of the server has failed.

Action:
Check the server log to determine the cause of the subsystem failure.

BEA-310007
Subsystem {0} in partition {1} has failed because of: {2} However, notification did not occur because {0} was not registered with the HealthMonitorService.

Category:
Health

Cause:
One of the subsystems of the server has failed.

Action:
Check the server log to determine the cause of the subsystem failure. MigratableTargets may need to be manually moved, since the automatic migration subsystem requires HealthMonitor notification to work properly.

BEA-310008
Non-critical subsystem {0} in partition {1} has failed. Reason: {2}

Category:
Health

Cause:
One of the non-critical subsystems of the server has failed.

Action:
Check the server log to determine the cause of the subsystem failure.

BEA-310009
Restart of persistent store {0} and its upper services in partition {1} has failed after {2} restart attempts in {3} seconds. Reason: {4}

Category:
Health

Cause:
Restart of persistent store and its upper services has failed.

Action:
Check the server log to determine the cause of the Restart failure.

BEA-310010
Persistent store "{0}" in partition "{1}" is reporting a failure. It will attempt up to {2} restarts with {3} seconds between each attempt.

Category:
Health

Cause:
This is an informational message.

Action:
No action is required.

BEA-310011
Persistent store "{0}" in partition "{1}" and the services that depend on this store have been restarted successfully.

Category:
Health

Cause:
This is an informational message.

Action:
No action is required.

BEA-320000
The Diagnostics subsystem is initializing on Server {0}.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320001
The ServerDebug service initialized successfully.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320002
The Diagnostics subsystem is stopping on Server {0}.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320004
The following unexpected exception was thrown: {0}

Category:
Diagnostics

Cause:
An exception was thrown unexpectedly.

Action:
Take appropriate action based on the unexpected exception message.

BEA-320005
Diagnostic monitor of unknown type {1} used in instrumentation scope {0}.

Category:
Diagnostics

Cause:
The Diagnostic Monitor library is probably out of date.

Action:
Update the Diagnostic Monitor library.

BEA-320008
Error occurred while collecting diagnostic metrics:

Category:
Diagnostics

Cause:
An error occurred while constructing a Harvester instance.

Action:
Ensure that all harvester configuration parameters are set appropriately.

BEA-320009
The elapsed time of the last snapshot of diagnostic metrics exceeded the configured sample period by the following number of milliseconds: {0}.

Category:
Diagnostics

Cause:
Harvested MBeans and/or DataSources are taking too long to return sampled attribute values.

Action:
Increase the sample period window.

BEA-320010
An error occurred while generating a diagnostic image: {0}

Category:
Diagnostics

Cause:
Permissions were abruptly changed on the zip/directory. The file system does not have sufficient disk space to continue writing the image.

Action:
Allocate sufficient disk space and provide the proper permissions to create the image zip file.

BEA-320011
The following diagnostic image destination directory could not be created: {0}

Category:
Diagnostics

Cause:
You have not given write permissions to the absolute path for the default directory, or you have not allocated sufficient disk space for the directory to be created.

Action:
You must give write permissions to the absolute path for the default directory if no configured destination directory is specified. You must also allocate sufficient disk space for the default directory to be created if no destination directory is specified.

BEA-320012
The following destination directory for diagnostic images could not be read or written to: {0} or there is not enough free space available to create the diagnostic image.

Category:
Diagnostics

Cause:
The directory was not created or directory read and write permissions were not given to the directory.

Action:
Create the destination directory with the appropriate read and write permissions.

BEA-320013
Diagnostic image capture was attempted during a lockout period.

Category:
Diagnostics

Cause:
The ImageManager has locked image captures for a specified number of minutes.

Action:
The lockout period must expire before a new image capture request is accepted.

BEA-320014
Lockout of {0} above allowed maximum lockout minutes for image captures.

Category:
Diagnostics

Cause:
The specified a number of minutes exceeds the maximum allowed lockout minutes.

Action:
Specify a lockout period between the minimum and maximum.

BEA-320015
Lockout of {0} below allowed minimum lockout minutes for image captures.

Category:
Diagnostics

Cause:
The specified a number of minutes falls below the minimum allowed lockout minutes.

Action:
Specify a lockout period between the minimum and maximum.

BEA-320016
Creating diagnostic image in {0} with a lockout minute period of {1}.

Category:
Diagnostics

Cause:
A FirstFailure has occurred, a diagnostic image notification handler was configured, or a capture image method was explicitly invoked on ImageManager.

Action:
No action is required. The diagnostic image capture request will be scheduled and executed.

BEA-320018
Instrumentation engine configuration {0} could not be parsed due to: {1}

Category:
Diagnostics

Cause:
The instrumentation engine configuration is possibly malformed.

Action:
Check for other log messages that give more information about the failure.

BEA-320019
Code generator class {1} for standard monitor {0} could not be found.

Category:
Diagnostics

Cause:
The standard monitor code generator was not on the class path.

Action:
Check for other log messages that give more information about the failure.

BEA-320020
Code generator {1} for standard monitor {0} could not be instantiated.

Category:
Diagnostics

Cause:
The standard monitor code generator is missing the default constructor.

Action:
Check for other log messages that give more information about the failure.

BEA-320021
The code generator {1} could not be accessed for standard monitor {0}.

Category:
Diagnostics

Cause:
The standard monitor code generator implementation has problems.

Action:
Check for other log messages that give more information about the failure.

BEA-320022
An error was encountered while creating SerialVersionUID for class {0}.

Category:
Diagnostics

Cause:
SerialVersionUID for a class could not be created.

Action:
Check for other log messages that give more information about the failure.

BEA-320023
File {0} does not contain a valid Java class

Category:
Diagnostics

Cause:
The file does not contain a valid Java class.

Action:
Make sure that the file being instrumented is a valid Java class file.

BEA-320024
Class in file {0} could not be instrumented.

Category:
Diagnostics

Cause:
This can happen when the input file or output file cannot be read from or written to.

Action:
Check the file permissions and disk space.

BEA-320025
Input file {0} for instrumentation engine cannot be found.

Category:
Diagnostics

Cause:
The input class file does not exist.

Action:
Provide the correct path to the input class file.

BEA-320026
Monitor {0} could not be found in instrumentation engine configuration.

Category:
Diagnostics

Cause:
The monitor name may be misspelled.

Action:
Specify the correct monitor name on the command line.

BEA-320030
Delegating monitor {1} in scope {0} allows using action of type {2}, which does not exist.

Category:
Diagnostics

Cause:
A delegating monitor was not properly configured in the instrumentation engine configuration.

Action:
Check for other log messages that give more information about the failure.

BEA-320031
An attempt to add a monitor of type {1} to instrumentation scope {0} failed because the monitor already exists in the scope.

Category:
Diagnostics

Cause:
Instrumentation configuration was incorrect.

Action:
Remove multiple monitor entries with same types from the instrumentation scope configuration.

BEA-320032
Attempt to add duplicate action {2} to monitor {1} in scope {0} failed.

Category:
Diagnostics

Cause:
Instrumentation scope configuration is incorrect. It has duplicate actions attached to the same monitor.

Action:
Remove duplicate actions attached to the same monitor.

BEA-320033
Attempt to attach incompatible action of type {2} to a delegating monitor of type {1} in scope {0}.

Category:
Diagnostics

Cause:
Instrumentation configuration is incorect.

Action:
Make sure that only compatible actions are used with delegating monitors.

BEA-320034
Instrumentation engine configuration {0} could not be parsed. {1}

Category:
Diagnostics

Cause:
The instrumentation configuration is malformed.

Action:
Check for other log messages that give more information about the failure.

BEA-320035
Instrumentation configuration {0} could not be read.

Category:
Diagnostics

Cause:
The instrumentation configuration is missing or invalid.

Action:
Check for other log messages that give more information about the failure.

BEA-320036
Instrumented method {1}{2} in class {0} exceeds size limit. Original method is preserved.

Category:
Diagnostics

Cause:
The original method is too large to begin with. The class to which it belongs is probably generated by a generator program.

Action:
If possible, split the method into multiple methods. Exclude the class from instrumentation to speed up the instrumentation process.

BEA-320037
Class bytes for {0} do not conform to class format.

Category:
Diagnostics

Cause:
The class file is corrupt.

Action:
Make sure that the class file is not corrupt.

BEA-320038
Could not instrument class {0}

Category:
Diagnostics

Cause:
This is a general instrumentation failure.

Action:
Check for other log messages that give more information about the failure.

BEA-320039
Invalid class inclusion pattern(s) for instrumentation engine/scope {0}. Disabling instrumentation in scope {0}.

Category:
Diagnostics

Cause:
Inclusion patterns are malformed.

Action:
Specify inclusion patterns in the correct format.

BEA-320040
Invalid class exclusion pattern(s) for instrumentation engine/scope {0}. Disabling instrumentation in scope {0}.

Category:
Diagnostics

Cause:
One or more exclusion patterns are malformed.

Action:
Specify exclusion patterns in the correct format.

BEA-320041
Invalid lockout minutes {0} specified in image notification. Image capture was not performed.

Category:
Diagnostics

Cause:
The value is invalid.

Action:
Recreate the notification with a valid lockout minutes value.

BEA-320042
Invalid diagnostic image location {0} specified in notification, exception message is {1}. Image capture was not performed.

Category:
Diagnostics

Cause:
The value is not a valid directory or file name.

Action:
Recreate the notification with a valid image location. Take appropriate action based on the exception message.

BEA-320043
Image notification was not performed because the image capture was attempted before the lockout time expired. The exception message is {0}

Category:
Diagnostics

Cause:
An image capture was attempted before the lockout period expired.

Action:
Recreate the image notification with a smaller value for lockout minutes. Optionally, use the watch alarm feature to ensure that the notification does not occur again before the lockout period has expired.

BEA-320044
Error occurred while performing a watch notification:

Category:
Diagnostics

Cause:
An error occurred while performing the operations required for the notification.

Action:
Take appropriate action based on the unexpected exception message.

BEA-320047
Mail notification has not been sent due to an error that occurred while creating or sending a mail message:

Category:
Diagnostics

Cause:
An error occurred while performing the mail operations required for the notification.

Action:
Verify the MailSession properties and email destination. Take appropriate action based on the Messaging exception message.

BEA-320048
JMS notification message has not been sent due to an error that occurred while creating a JMS map message:

Category:
Diagnostics

Cause:
An error occurred while performing the JMS operation.

Action:
Verify the JMS queue and connection factory configuration settings in the JMS notification. Take appropriate action based on the JMS exception message.

BEA-320049
An exception occurred sending JMS notification message. Reinitializing JMS objects and retrying.

Category:
Diagnostics

Cause:
An error occurred while sending the JMS message.

Action:
Look for additional error messages in the log from the reinitialization or resend of the message.

BEA-320052
An error occurred while initializing a SMTP notification:

Category:
Diagnostics

Cause:
The mail session is incorrectly configured or not available.

Action:
Ensure that the mail session JNDI name is correct. Ensure that the mail session MBean properties are valid. Take appropriate action based on the exception message.

BEA-320053
The SNMP Agent is not configured. The trap for the SNMP Watch notification cannot be sent.

Category:
Diagnostics

Cause:
The SNMP Agent is not enabled.

Action:
Enable the SNMP Agent using the console.

BEA-320054
An error occurred while sending an SNMP notification:

Category:
Diagnostics

Cause:
An exception occurred in the SNMP Agent when sending the SNMP trap to the configured trap destinations.

Action:
Ensure that the trap destinations are configured correctly. Take appropriate action based on the exception message.

BEA-320055
Could not read or create index on log file {0}.

Category:
Diagnostics

Cause:
The drive may be full or the directory is not writable.

Action:
Check whether the drive is full or the directory is not writable.

BEA-320056
Log index file {0} has an invalid magic number.

Category:
Diagnostics

Cause:
The index file is corrupt or invalid.

Action:
Delete the corrupt index file.

BEA-320057
Log index file {0} contents are inconsistent with its header.

Category:
Diagnostics

Cause:
The index file is corrupt or truncated.

Action:
Delete the index file.

BEA-320058
Could not parse log record: {0}

Category:
Diagnostics

Cause:
The log record is malformed.

Action:
Check for other log messages that give more information about the failure.

BEA-320063
An attempt to add watch {0} failed because the watch has already been defined.

Category:
Diagnostics

Cause:
Two different watch definitions have the same name.

Action:
Remove one of the watch entries that has the same name.

BEA-320064
Watch {0} could not be created due to the following unexpected exception: {1}

Category:
Diagnostics

Cause:
An exception occurred unexpectedly.

Action:
Take appropriate action based on the unexpected exception message.

BEA-320066
An attempt to add notification {0} failed because the notification has already been defined.

Category:
Diagnostics

Cause:
Two different notification definitions have the same name.

Action:
Remove one of the notification entries with the same name.

BEA-320068
Watch "{0}" in module "{1}" with severity "{2}" on server "{3}" has triggered at {4}. Notification details: {5}

Category:
Diagnostics

Cause:
A configured watch has evaluated to true and has triggered.

Action:
No action is required.

BEA-320069
Watch {0} contains an invalid notification {1} that is not defined.

Category:
Diagnostics

Cause:
The notification does not exist.

Action:
Define the notification or remove the notification from the watch.

BEA-320070
Error occurred while performing notification {1} for watch {0}. Notification may not have completed.

Category:
Diagnostics

Cause:
An exception occurred while performing the notification.

Action:
Validate the definition for the specified watch and notification. Take appropriate action based on the error message.

BEA-320071
Error occurred while creating watch notification {0}. Notifications may not have completed for this watch.

Category:
Diagnostics

Cause:
An exception occurred while creating the watch notification.

Action:
Validate the definition for the specified watch and notification. Take appropriate action based on the error message.

BEA-320073
Error while locating a record for timestamp {0} in the archive

Category:
Diagnostics

Cause:
There is a misconfigured or missing data archive for harvested data.

Action:
Check that the harvested data archive exists.

BEA-320074
Error while executing query.

Category:
Diagnostics

Cause:
A runtime error occurred while executing a query.

Action:
Check for other log messages that give more information about the failure.

BEA-320075
Error while reading a record from the archive

Category:
Diagnostics

Cause:
The harvested data archive may be corrupt.

Action:
Reconfigure the harvested data archive.

BEA-320076
Could not initialize index information for harvester data archive.

Category:
Diagnostics

Cause:
The harvested data archive may be corrupt.

Action:
Reconfigure the harvested data archive.

BEA-320077
Initialized the Diagnostic Accessor Service.

Category:
Diagnostics

Cause:
This is a normal operation.

Action:
No action is needed.

BEA-320078
Could not initialize the Diagnostic Accessor Service Runtime during server startup.

Category:
Diagnostics

Cause:
The exception message includes the details about the cause of this problem.

Action:
Take corrective action based on the exception stack trace.

BEA-320079
Watch "{0}" rule expression evaluation failed with an exception. No notifications will be performed for this watch. The exception is:

Category:
Diagnostics

Cause:
An exception occurred during rule evaluation.

Action:
Verify that the rule expression is valid. Take appropriate action based on the exception message.

BEA-320080
The log type {0} is unknown. Unable to lookup the DiagnosticDataAccessRuntimeMBean instance.

Category:
Diagnostics

Cause:
This message indicates that the logical name that was specified to look up the DiagnosticDataAccessRuntimeMBean is not correct.

Action:
Verify that the log type is valid. Take appropriate action based on the exception message.

BEA-320082
Configuration for diagnostic monitor {0} in instrumentation scope {1} has errors. The exception is:

Category:
Diagnostics

Cause:
An exception occurred while reading the configuration of a diagnostic monitor in a scope.

Action:
Verify that the configuration for the diagnostic monitor is valid.

BEA-320083
Custom diagnostic monitor {0} in instrumentation scope {1} has missing or invalid location attribute.

Category:
Diagnostics

Cause:
There is a missing or invalid value of the "location" attribute of a custom diagnostic monitor.

Action:
Verify that the "location" attribute of the custom monitor has a correct value.

BEA-320084
The user {0} does not have authorization to view the logs.

Category:
Diagnostics

Cause:
A user with insufficient authorization attempted to access the server logs.

Action:
Ensure that the right users are granted access to view the logs.

BEA-320085
The diagnostic data is accessible only through https in Production mode.

Category:
Diagnostics

Cause:
An attempt to access the diagnostic data was made over a non-secure protocol in Production mode.

Action:
Ensure that the SSL is enabled in Production mode and that the servlet is accessed only over a secure protocol.

BEA-320086
The monitor type {1} in scope {0} contains unacceptable characters.

Category:
Diagnostics

Cause:
The monitor type contains unacceptable characters. It must start with an alphabetic character, followed by alphanumeric or underscore characters.

Action:
Fix the assigned monitor type, which must start with an alphabetic character, optionally followed by alphanumeric or underscore characters.

BEA-320087
The cursor {0} has timed out and is being removed from the registry of open cursors.

Category:
Diagnostics

Cause:
This message is emitted when a cursor has not been invoked and is being removed to free up the associated resources.

Action:
Ensure that fetch is not called anymore on the closed cursor.

BEA-320088
The cursor with name {0} does not exist.

Category:
Diagnostics

Cause:
The cursor could have timed out or been closed by the user explicitly. Otherwise, or an invalid name has been provided.

Action:
Invoke the fetch method with the name of a valid cursor.

BEA-320091
Attempt to use unknown action {1} in action group {0}

Category:
Diagnostics

Cause:
This is due to an incorrect or incomplete instrumentation engine configuration.

Action:
Check for other log messages that give more information about the failure.

BEA-320092
Monitor {0} used empty or non-existent action group {1}

Category:
Diagnostics

Cause:
This is due to an incorrect or incomplete instrumentation engine configuration.

Action:
Check for other log messages that give more information about the failure.

BEA-320093
Encountered problem while reading attributes of monitor {0}. Attributes: {1}

Category:
Diagnostics

Cause:
Possibly invalid attribute names were specified with the diagnostic monitor.

Action:
Specify correct attributes for the diagnostic monitor.

BEA-320094
Could not initialize server instrumentation scope.

Category:
Diagnostics

Cause:
Internal error

Action:
Check for other log messages that give more information about the failure.

BEA-320096
Cannot create custom monitor {0} in server instrumentation scope.

Category:
Diagnostics

Cause:
Custom monitors can not be defined in the server instrumentation scope.

Action:
Remove the custom monitor definition from the server instrumentation scope.

BEA-320097
Monitor {0} can be created only in an application instrumentation scope. It cannot be created in server instrumentation scope.

Category:
Diagnostics

Cause:
An attempt was made to create a monitor in the server scope, but it can only be created in the application scope.

Action:
Remove the monitor definition from the server instrumentation scope.

BEA-320098
Monitor {0} can be created only in server instrumentation scope. It can not be created in application instrumentation scope {1}.

Category:
Diagnostics

Cause:
An attempt was made to create a monitor in the application scope, but it can only be created in the server scope.

Action:
Remove the monitor definition from the application instrumentation scope.

BEA-320100
Configuration for JDBC-based diagnostic archives is invalid or incomplete. Using file based diagnostic archive.

Category:
Diagnostics

Cause:
The configuration for JDBC-based diagnostic archives is invalid or incomplete.

Action:
Fix the configuration for JDBC-based diagnostic archives.

BEA-320101
Attempt to target more than one WLDFSystemResource to server {0}.

Category:
Diagnostics

Cause:
This error indicates that an invalid targeting was specified for a WLDFSystemResource.

Action:
Ensure that only one WLDFSystemResource is targeted to a server.

BEA-320102
An error occcurred when trying to access the diagnostic data while executing the query expression {0}.

Category:
Diagnostics

Cause:
The query was not specified properly.

Action:
Ensure that the query is valid.

BEA-320103
An error occurred while creating the DiagnosticDataRuntimeMBean instance with the given logical name {0}.

Category:
Diagnostics

Cause:
The logical name is not a valid parameter or an error occurred while reading the diagnostic data.

Action:
Ensure that the logical name is valid and take corrective action based on the reported error.

BEA-320104
An error occurrred when invoking the log4j operation while activating/deactivating log watch rules.

Category:
Diagnostics

Cause:
The log4j libraries may not be in the CLASSPATH.

Action:
Ensure that the log4j libraries are available when using Log watch rules with Log4j enabled.

BEA-320105
The watch rule expression {0} is not valid.

Category:
Diagnostics

Cause:
The watch rule expression does not conform to the correct syntax.

Action:
Specify a valid watch rule expression.

BEA-320106
The watch notification configuration already contains a notification with the given name {0}.

Category:
Diagnostics

Cause:
The name for the WLDFNotification you are adding is not unique.

Action:
Specify a unique name for the notification.

BEA-320111
The elapsed time since the last Harvester cycle ({0} milliseconds) is unacceptably short. Skipping this cycle in order to smooth out the responses.

Category:
Diagnostics

Cause:
The previous Harvesting process consumed a large percentage of the sample period. This can happen for 3 reasons: 1) you requested that a very large amount of data be harvested, 2) the system is consistently slow for some reason, 3) an intermittent service caused the process to slow down temporarily (for example, for garbage collection).

Action:
No action is required. The Harvester will compensate by skipping cycles that occur too soon. If this happens consistently, either because you are harvesting a large amount of data, or the Harvester is running on a slow system, you can either increase the samplePeriod or increase system resources.

BEA-320113
The type {0} is no longer being harvested.

Category:
Diagnostics

Cause:
This is caused by an earlier problem. Sufficient log messages should have been issued at the point of failure to allow the problem to be debugged. Note that the type will remain deleted until the Harvester configuration is reloaded. At that time, if the problem is not yet resolved, this message may be issued again.

Action:
No action is required. Typically, this type of error will cause some of the requested data to not be harvested. It is advisable to fix the issue.

BEA-320114
Initializing the Diagnostics Harvester.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320115
The Harvester is configured to be disabled.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320116
Harvester type {0} is configured to be disabled. No harvesting will occur for this type.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320117
The Harvester is being disabled because there are no valid Harvestable types configured.

Category:
Diagnostics

Cause:
This may occur because you did not provide any type specifications, or, if type specifications were provided, none of the specified types were harvestable.

Action:
No action is required.

BEA-320118
The Harvester timer has been initiated for an interval of {0} milliseconds.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320119
The Harvester is now in a {0} state.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320122
Unable to harvest attribute {0} on item {1} due to errors. This attribute will no longer be harvested.

Category:
Diagnostics

Cause:
The actual problem occurred at a previous point in time. Sufficient messages should have been issued at the point of failure to facilitate debugging the problem.

Action:
No action is required. Typically, this type of error will cause some of the requested data to not be Harvested. It is advisable to fix the issue.

BEA-320123
Could not add MBean instance {0} to the harvested instance list for type {1}: {2}.

Category:
Diagnostics

Cause:
The actual problem occurred at a previous point in time. Sufficient messages should have been issued at the point of failure to facilitate debugging the problem.

Action:
No action is required. Typically, this type of error will cause some of the requested data to not be Harvested. It is advisable to fix the issue.

BEA-320124
The harvester has discovered a new instance of harvested type {1} named {0}.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320125
Attention: {0}

Category:
Diagnostics

Cause:
This indicates a system error, not a user error. Further investigation is required to determine the cause.

Action:
In most cases, you should be able to turn on Harvester debug to obtain additional information.

BEA-320126
Reinitializing the Diagnostics Harvester.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320127
An error occurred while generating Image Source {0} as part of the diagnostic image zip file:

Category:
Diagnostics

Cause:
An unexpected error occurred while the subsystem was collecting or persisting the diagnostic image source information.

Action:
Take appropriate action based on the unexpected exception message.

BEA-320128
The WLDFResourceBean is not found for the WLDFSystemResource {0}.

Category:
Diagnostics

Cause:
This error is caused by either a deleted or corrupt WLDF descriptor file.

Action:
Ensure that the descriptor file exists for the WLDFSytemResource and that it conforms to the expected schema.

BEA-320129
Instrumentation module {0} created.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320130
Instrumentation module {0} is disabled.

Category:
Diagnostics

Cause:
This instrumentation module for server or application is disabled.

Action:
No action is required.

BEA-320131
Instrumentation module {0} is configured, but disabled because a WLDF system resource is not targeted to the server, or its instrumentation component is not enabled.

Category:
Diagnostics

Cause:
There is no WLDF system resource targeted to the server, or its instrumentation component is disabled.

Action:
Check if there is a WLDF system resource targeted to the server and its instrumentation component is enabled.

BEA-320132
Updating classes within scope {0} since its instrumentation configuration has changed.

Category:
Diagnostics

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320133
Could not instantiate one of the known accessors during server startup.

Category:
Diagnostics

Cause:
The exception message includes the details about the cause of this problem.

Action:
Take corrective action based on the exception stack trace.

BEA-320134
An error occurred while creating a domain log handler: {0}.

Category:
Diagnostics

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Check for other log messages that give more information about the failure.

BEA-320135
JDBC-based {0} archive could not be created. Falling back on persistent store based archive.

Category:
Diagnostics

Cause:
This happens when the JDBC data source to be used with the archive is misconfigured or unavailable, or database tables are not available.

Action:
Ensure that the JDBC data source is correctly configured and available, and that database tables have been created prior to use.

BEA-320136
Class {0} could not be instrumented, due to reason: "{1}".

Category:
Diagnostics

Cause:
This can happen because the class may contain constructs that are unsafe to transform, for example, custom attributes.

Action:
Ensure that class does not have custom attributes or other such constructs.

BEA-320137
Invalid class inclusion pattern(s) for instrumentation monitor {1} in scope {0}. Disabling instrumentation in scope {0}.

Category:
Diagnostics

Cause:
There are malformed inclusion patterns in the instrumentation monitor.

Action:
Specify inclusion patterns in the instrumentation monitor using the correct format.

BEA-320138
Invalid class exclusion pattern(s) for instrumentation monitor {1} in scope {0}. Disabling instrumentation in scope {0}.

Category:
Diagnostics

Cause:
There are malformed exclusion patterns in the instrumentation monitor.

Action:
Specify exclusion patterns in the instrumentation monitor using the correct format.

BEA-320139
Archive {0} is not found during a data retirement operation.

Category:
Diagnostics

Cause:
Data retirement may be configured for a custom archive that does not yet exist.

Action:
Ensure that the custom archive is created, or disable or remove this retirement configuration.

BEA-320140
Scheduling data retirement tasks as per configuration.

Category:
Diagnostics

Cause:
This is a normal operation.

Action:
No action is required.

BEA-320141
An error was encountered while performing age-based data retirement on archive {0}.

Category:
Diagnostics

Cause:
An error was encountered while performing age-based data retirement on the indicated archive.

Action:
Check for other log messages that give more information about the failure.

BEA-320142
An error was encountered while performing size-based data retirement on archive {0}.

Category:
Diagnostics

Cause:
An error was encountered while performing size-based data retirement on the indicated archive.

Action:
Check for other log messages that give more information about the failure.

BEA-320143
Scheduled {0} data retirement tasks as per configuration.

Category:
Diagnostics

Cause:
Finished processing the data retirement configuration.

Action:
No action is required.

BEA-320144
{0} operation started on archive {1}.

Category:
Diagnostics

Cause:
This is a normal operation.

Action:
No action is required.

BEA-320145
{0} operation completed on archive {1}. Retired {2} records in {3} ms.

Category:
Diagnostics

Cause:
This is a normal operation.

Action:
No action is required.

BEA-320146
Failed to register dye {0} at index {1}.

Category:
Diagnostics

Cause:
A dye with the same name or index already exists.

Action:
Check for other log messages that give more information about the failure.

BEA-320147
Instrumentation system is disabled because the instrumentation library is invalid.

Category:
Diagnostics

Cause:
The instrumentation engine configuration is corrupt or a required DyeInjection monitor cannot be found.

Action:
Check for other log messages that give more information about the failure.

BEA-320148
Required diagnostic monitor {0} is missing from the instrumentation library.

Category:
Diagnostics

Cause:
The instrumentation engine configuration is corrupt.

Action:
Check for other log messages that give more information about the failure.

BEA-320149
The DomainRuntime MBeanServer was not available for harvesting.

Category:
Diagnostics

Cause:
The DomainRuntime MBeanServer could not be loaded by the Harvester.

Action:
Check for other log messages that give more information about the failure.

BEA-320151
The instance name {0} in the Watch configuration {1} is invalid.

Category:
Diagnostics

Cause:
The instance name or instance-name pattern was not a valid JMX ObjectName or instance name pattern supported by the WLDF Watch and Notifications framework.

Action:
Check that the instance name is a valid ObjectName, or an instance-name pattern as specified in the WLDF Watch and Notifications framework documentation.

BEA-320152
An unexpected exception occurred while removing the set of watched metrics "{0}" from the harvester: {1}

Category:
Diagnostics

Cause:
An attempt was made to delete a set of watched metrics from the harvester that has already been removed, or one that was never activated within the harvester.

Action:
Check for other log messages that give more information about the failure.

BEA-320153
Instrumentation configuration for application "{0}" has changed. However, it will take effect only after redeploying the application, since hot-swap is not enabled.

Category:
Diagnostics

Cause:
Hot-swap is not enabled.

Action:
Redeploy the application, or restart the server with the diagnostic agent on the command line to enable hot-swap.

BEA-320154
Class redefinition failed after instrumentation configuration was changed for application "{0}" : {1}

Category:
Diagnostics

Cause:
An unexpected exception occurred while redefining classes after the instrumentation configuration was updated.

Action:
Check for other log messages that give more information about the failure.

BEA-320155
Inconsistent instrumentation handling information was specified in the same pointcut definition for {0} : {1} : {2}.

Category:
Diagnostics

Cause:
The instrumentation configuration contains a pointcut definition that specifies conflicting information for the method.

Action:
Review the pointcuts that specify the method listed in the error, and verify that there are not multiple definitions for the methods with which they conflict. For example, one indicating an argument is not-sensitive while another indicates it is.

BEA-320156
The renderer class {0} could not be loaded due to {1}, the following renderer will be used instead: {2}.

Category:
Diagnostics

Cause:
The instrumentation configuration specified a renderer class that either was not found, is not accessible, or is not a renderer.

Action:
Verify that the renderer class is correctly specified in the instrumentation configuration and that it is available to the server classloader.

BEA-320157
An error occurred when registering the log4j for data gathering operations.

Category:
Diagnostics

Cause:
The log4j libraries may not be in the CLASSPATH.

Action:
Ensure that the log4j libraries are available when using Log watch rules with Log4j enabled.

BEA-320158
An error was detected while capturing the flight recorder image.

Category:
Diagnostics

Cause:
The specified exception provides details on the error that was encountered.

Action:
Review the provided exception information to determine the cause and action to take.

BEA-320159
An error was detected while initializing the flight recording.

Category:
Diagnostics

Cause:
The specified exception provides details on the error that was encountered.

Action:
Review the provided exception information to determine the cause and action to take.

BEA-320160
The type-based renderer class {0} for type {1} could not be loaded due to {1}, that type-based renderer will not be used.

Category:
Diagnostics

Cause:
The instrumentation configuration specified a type-based renderer class that either was not found, is not accessible, or is not a renderer. It may also be that the type itself was not found or loadable.

Action:
Verify that the type-based renderer class and type class are correctly specified in the instrumentation configuration and that they are available to the server classloader.

BEA-320161
A legacy Spring instrumentation API was called for an unknown method {0}.

Category:
Diagnostics

Cause:
A legacy Spring instrumentation API was called for an unknown method {0}.

Action:
Instrument Spring using the tools in the current release.

BEA-320162
A legacy Spring instrumentation API was called.

Category:
Diagnostics

Cause:
A legacy Spring instrumentation API was called.

Action:
Legacy Spring features should function normally, but you should instrument Spring using the tools in the current release.

BEA-320163
Wildcarded types are not allowed to be marked as being insensitive with %.

Category:
Diagnostics

Cause:
A % character was specified for a wildcarded type, such as an asterisk or ellipses. This is not allowed, as it could lead to inadvertantly exposing a type that should be treated as being sensitive.

Action:
Review the pointcuts that specify the % character to ensure that it is not supplied for any types that are wildcarded using an asterisk or ellipses.

BEA-320164
Circular class load detected during stackmap frame computation for {0}.

Category:
Diagnostics

Cause:
An attempt was made to class load the class currently being instrumented. This is not supported.

Action:
Do not instrument the class that encountered the cycle.

BEA-320165
Received an unexpected error dispatching an Instrumentation event for Watch rule processing: {0}

Category:
Diagnostics

Cause:
An exception occurred while dispatching a WLDF Instrumentation event for Watch rule processing.

Action:
Check the server log for details on the error.

BEA-320166
Received an unexpected error dispatching an logging event for Watch rule processing: {0}

Category:
Diagnostics

Cause:
An exception occurred while dispatching a WLDF log event for Watch rule processing.

Action:
Check the server log for details on the error.

BEA-320167
Expected monitors were not instrumented : {0}

Category:
Diagnostics

Cause:
Monitors which were specified as being expected to be instrumented were not instrumented.

Action:
Review the instrumentation configuration and the code being instrumented, and then verify that all dependencies are available in the classpath to allow the instrumentor to walk the class hierarchy for inheritance matches.

BEA-320168
Disabling instrumentation on application "{0}" in partition "{1}" since it may contain shareable classloaders.

Category:
Diagnostics

Cause:
The deployment descriptor of this application may have indicated that its classloaders may be shared with applications in other partitions.

Action:
If application instrumentation for this application is needed, remove shareable classloader definitions from the weblogic-application.xml deployment descriptor.

BEA-320169
Activating dynamic debug patch "{0}" at system level.

Category:
Diagnostics

Cause:
Dynamic debug patch is being activated at the system level.

Action:
No action is required.

BEA-320170
Activating dynamic debug patch "{0}" at application "{1}"

Category:
Diagnostics

Cause:
Dynamic debug patch is being activated at the application level.

Action:
No action is required.

BEA-320171
Activating dynamic debug patch "{0}" at module "{2}" in application "{1}"

Category:
Diagnostics

Cause:
Dynamic debug patch is being activated at the indicated module in the indicated application.

Action:
No action is required.

BEA-320172
Activating dynamic debug patch "{0}" at application "{1}" in partition "{2}"

Category:
Diagnostics

Cause:
Dynamic debug patch is being activated at the indicated application in the indicated partition.

Action:
None

BEA-320173
Activating dynamic debug patch "{0}" at module "{2}" in application "{1}" in partition "{3}"

Category:
Diagnostics

Cause:
Dynamic debug patch is being activated at the indicated module in the indicated application in the indicated partition.

Action:
No action is required.

BEA-320174
Successfully activated debug patch "{0}".

Category:
Diagnostics

Cause:
Debug patch was successfully activated.

Action:
No action is required.

BEA-320175
Failed to activate dynamic debug patch "{0}".

Category:
Diagnostics

Cause:
Classes in the dynamic debug patch may be structurally different than the original classes.

Action:
Check whether the class(es) in the dynamic debug patch are structurally different than the original classes.

BEA-320176
Deactivating dynamic debug patch "{0}" at system level.

Category:
Diagnostics

Cause:
Dynamic debug patch is being deactivated at the system level.

Action:
No action is required.

BEA-320177
Deactivating dynamic debug patch "{0}" at application "{1}"

Category:
Diagnostics

Cause:
Dynamic debug patch is being deactivated at the application level.

Action:
No action is required.

BEA-320178
Deactivating dynamic debug patch "{0}" at module "{2}" in application "{1}"

Category:
Diagnostics

Cause:
Dynamic debug patch is being deactivated at the indicated module in the indicated application.

Action:
No action is required.

BEA-320179
Deactivating dynamic debug patch "{0}" at application "{1}" in partition "{2}"

Category:
Diagnostics

Cause:
Dynamic debug patch is being disabled at the indicated application in the indicated partition.

Action:
No action is required.

BEA-320180
Deactivating dynamic debug patch "{0}" at module "{2}" in application "{1}" in partition "{3}"

Category:
Diagnostics

Cause:
Dynamic debug patch is being deactivated.

Action:
No action is required.

BEA-320181
Successfully deactivated debug patch "{0}".

Category:
Diagnostics

Cause:
Debug patch was successfully deactivated.

Action:
No action is required.

BEA-320182
Failed to deactivate dynamic debug patch "{0}".

Category:
Diagnostics

Cause:
The indicated dynamic debug patch was not deactivated.

Action:
Check for other log messages that give more information about the failure.

BEA-320183
Debug patch "{0}" contains unknown classes: "{1}

Category:
Diagnostics

Cause:
Debug patch contains unknown classes that cannot be found on the classpath.

Action:
Contact the patch producers and have them address this issue.

BEA-320184
Failed to open diagnostic store file {0} due to reason: {1}. Re-trying to open..

Category:
Diagnostics

Cause:
This usually happens when the file is locked at the system level.

Action:
Identify the entity holding the lock and release the lock. This may be a system-dependent operation.

BEA-320185
Failed to open diagnostic store file {0} after {1} attempts. Some diagnostics features will be unavailable.

Category:
Diagnostics

Cause:
This usually happens when the file is locked at the system level.

Action:
Identify the entity holding the lock and release the lock. This may be a system dependent operation.

BEA-320186
Unable to find canonical path to diagnostic store directory {0}

Category:
Diagnostics

Cause:
The specified store directory path is not correct.

Action:
Specify the correct store directory path.

BEA-320187
ClassInfo for {0} is not available.

Category:
Diagnostics

Cause:
The ClassInfo for the class was not able to be retrieved or computed.

Action:
Enable instrumentation debug logging to determine the root cause.

BEA-320188
Long RID value with {0} components was created.

Category:
Diagnostics

Cause:
RID values grow during DiagnosticContext propagation, which are outbound calls to other JVMs or when Work is scheduled. Extremely long RID values may be expected but if they are growing rapidly, this may indicate a problem if they are growing unbounded. Note that the first occurrence of this message is reported immediately. After that it is throttled and only reported periodically if further growth is being seen. A corresponding log event is also produced to the FlightRecorder.

Action:
Enable DiagnosticContext debug and review the FlightRecorder data to look for JFRDebugEvents which indicate extreme RID growth and where it is seen. Pay particular attention to the scheduling of work from daemon threads. These can cause RID growth and may require that the daemon thread call DiagnosticContextHelper.handleLocalContextAsNonInheritable() to prevent propagating the Context.

BEA-320189
Log file or rotation directory for accessor {0} changed, but the accessor failed to adapt to the change.

Category:
Diagnostics

Cause:
There may have been an error while refreshing the accessor due to an internal WebLogic error.

Action:
Enable DebugDiagnosticAccessor and DebugDiagnosticArchive and review logs to get more information on the possible cause of the internal WebLogic error leading to this error.

BEA-320190
Failed to close diagnostic store.

Category:
Diagnostics

Cause:
Failed to close diagnostic store, likely to be due to an internal error.

Action:
Review logs to get more information on the possible cause of the internal WebLogic error leading to this error.

BEA-320200
Action {0} of type {1} not valid for current WLDF deployment, ignoring.

Category:
DiagnosticsWatch

Cause:
The action type requested may not be valid for the WLDF deployment; for example, this can happen if the action is deployed on a managed server, but is only valid deployed within the administration server.

Action:
Check the action documentation, and revise the Watch and/or action configuration accordingly.

BEA-320201
An unexpected error occurred while instantiating action {1} for action type {0}: {2}

Category:
DiagnosticsWatch

Cause:
An unexpected error occurred while instantiating the specified action instance.

Action:
Check the error in the server logs and make any necessary configuration changes.

BEA-320202
Map entry string {0} is not valid.

Category:
DiagnosticsWatch

Cause:
A Map object entry in the WLDFActionBean did not have the proper form.

Action:
Fix the entry in the WLDF System Resource descriptor.

BEA-320203
The timeout period of {1} seconds expired for action {0}, canceling the action execution.

Category:
DiagnosticsWatch

Cause:
The action did not complete withing the specified timeout interval.

Action:
Consider increasing the timeout for the action, or see if an error occurred during processing that needs to be addressed.

BEA-320204
Executing action {0} with timeout period {1} seconds.

Category:
DiagnosticsWatch

Cause:
This is an informational message.

Action:
No action required.

BEA-320205
An IOException occurred while communicating with server {0}, unable to query it for instances matching "{1}"

Category:
DiagnosticsWatch

Cause:
A network error occurred while attempting to communicate with server {0}. If the error persists, check the server logs and Node Manager logs.

Action:
Determine the source of the communication error and correct it if possible.

BEA-320206
An error occurred while executing the script action {0}: {1}

Category:
DiagnosticsWatch

Cause:
The configured script was not executed successfully. This may be due to an error in the action configuration or an error that was encountered within the script itself.

Action:
Check the action configuration, and ensure that the script is available and has executable permissions.

BEA-320207
The script action {0} was interrupted during execution, exception: {1}

Category:
DiagnosticsWatch

Cause:
The script action may have timed out, or was abruptly terminated.

Action:
Check the error message for details about what may have caused execution to be interrupted.

BEA-320208
An invalid action configuration type {0} was passed into the ScriptAction service, expected a configuration of type {1}.

Category:
DiagnosticsWatch

Cause:
The ScriptAction service is not receiving the expected configuration type. This is likely a product defect and should be reported to My Oracle Support.

Action:
Contact My Oracle Support and provide them with the log file for further analysis.

BEA-320209
The executable path {1} for script action {0} is not valid.

Category:
DiagnosticsWatch

Cause:
The executable path indicated in the script action config is either missing or empty, or the path does not exist.

Action:
Check the action configuration and correct the executable path.

BEA-320210
Script action {0} execution of {1} completed with exit code {2}.

Category:
DiagnosticsWatch

Cause:
This is an informational message.

Action:
No action required.

BEA-320211
Script action {0} starting, stdout redirected to {1}, stderr redirected to {2}.

Category:
DiagnosticsWatch

Cause:
This is an informational message.

Action:
No action required.

BEA-320212
Cancel was requested for script action {0}, destroying the process.

Category:
DiagnosticsWatch

Cause:
The currently executing script action was cancelled externally, either by user request or by the action exceeding the configured timeout.

Action:
No action is required.

BEA-320213
REST notification {0} could not be delivered successfully to end point {1}. The response code is {2} and the detailed reason is {3}.

Category:
DiagnosticsWatch

Cause:
The REST end point may not be available or the REST notification is not configured correctly.

Action:
Take appropriate action based on the status code and detailed reason reported in the error.

BEA-320214
No action config present in action context.

Category:
DiagnosticsWatch

Cause:
There is likely a misconfiguration in the WLDFSystemResourceMBean associated with the action.

Action:
Check the configuration and resolve any issues.

BEA-320215
Scale down action {0} invoked for cluster {1} with scaling size {2} and timeout period of {3} seconds.

Category:
DiagnosticsWatch

Cause:
This is an informational message.

Action:
No action required.

BEA-320216
Scale down task {0} for cluster {1} complete, status: {2}

Category:
DiagnosticsWatch

Cause:
This is an informational message.

Action:
No action required.

BEA-320217
Invalid configuration {0} of type {1} passed to scale down action, expected an object of type {2}.

Category:
DiagnosticsWatch

Cause:
This was caused by an invalid configuration or a software defect.

Action:
Verify the action and policy configuration.

BEA-320218
No scale-up action config present in action context

Category:
DiagnosticsWatch

Cause:
There is likely a misconfiguration in the WLDFSystemResourceMBean associated with the action.

Action:
Check the configuration and resolve any issues.

BEA-320219
Invalid configuration {0} of type {1} passed to scale down action, expected an object of type {2}.

Category:
DiagnosticsWatch

Cause:
This was caused by an invalid configuration or a software defect.

Action:
Verify the action and policy configuration.

BEA-320220
Scale up action {0} invoked for cluster {1} with scaling size {2} and timeout period of {3} seconds.

Category:
DiagnosticsWatch

Cause:
This is an informational message.

Action:
No action required.

BEA-320221
Scale up task {0} for cluster {1} complete, status: {2}

Category:
DiagnosticsWatch

Cause:
The scale up task for the cluster is complete.

Action:
No action is required.

BEA-320222
Skipping actions processing for policy {0} since processing for a previous invocation is still in progress.

Category:
DiagnosticsWatch

Cause:
A previous invocation of the actions processing was found to be in progress. The new invocation was skipped.

Action:
No action is required.

BEA-320223
Another ThreadDumpAction is already in progress, so skipping execution of action {0}.

Category:
DiagnosticsWatch

Cause:
Another ThreadDumpAction is already in progress.

Action:
No action is required.

BEA-320224
Thread dump created at {0} by thread dump action {1} for policy {2} in diagnostics module {3}.

Category:
DiagnosticsWatch

Cause:
Thread dump is created due to execution of ThreadDumpAction.

Action:
Analyze generated thread dumps.

BEA-320225
Failed to write thread dump file {0}. {1}

Category:
DiagnosticsWatch

Cause:
Failed to write thread dump file due to permission or other file system problem.

Action:
Ensure appropriate permissions and sufficient disk space.

BEA-320226
Waiting for {0} seconds before capturing next thread dump.

Category:
DiagnosticsWatch

Cause:
Wait for configured time between successive thread dump captures.

Action:
No action is required.

BEA-320227
An attempt to capture a heap was made while another capture was already in progress.

Category:
DiagnosticsWatch

Cause:
An attempt to capture a new heap dump was made while another capture was already in progress; only one capture is allowed at a time.

Action:
No action is required.

BEA-320228
Capturing heap heap dump to file {0}, liveSetOnly={1}

Category:
DiagnosticsWatch

Cause:

Action:

BEA-320229
An unexpected exception occurred checking for the availability of the heap dump operation, heap dump action is not available: {0}

Category:
DiagnosticsWatch

Cause:
The HotSpot Diagnostic MBean is not available in the local JVM, therefore the heap dump action will not be available.

Action:
If the heap dump action is required, consider using a version of the Java Virtual Machine that supports the HotSpot Diagnostic MBean.

BEA-320230
Heap dump capture by action {1} for policy {2} in module {3} complete, located at {0}

Category:
DiagnosticsWatch

Cause:

Action:

BEA-320231
HeapDumpAction {0} was deployed on a JVM platform that does not suport it, the action will be disabled

Category:
DiagnosticsWatch

Cause:
HeapDumpAction {0} was deployed on a JVM platform that does not suport it.

Action:
If the action is required, consider using a JVM that supports the HotSpot Diagnostic MBean.

BEA-320232
The JMX Platform MBeanServer can not be found, heap dump actions are not available.

Category:
DiagnosticsWatch

Cause:
The Platform MBeanServer could not be found, check that the JVM supports the HotSpot Diagnostic MXBean.

Action:
If the heap dump action is required, consider using a JVM that supports the HotSpot Diagnostic MXBean.

BEA-320233
The dumpHeap() method could not be found, heap dump actions will not be available for this JVM.

Category:
DiagnosticsWatch

Cause:
The dumpHeap() method could not be found on the Hotspot Diagnostic MBean.

Action:
If the heap dump action is required, consider using a JVM that supports the HotSpot Diagnostic MXBean.

BEA-320234
The Hotspot Diagnostic MBean with ObjectName {0} could not be found, heap dump actions will not be available for this JVM

Category:
DiagnosticsWatch

Cause:
The JVM may not support heap dump operations.

Action:
If the heap dump action is required, consider using a JVM that supports the HotSpot Diagnostic MXBean.

BEA-320235
Caught unexpected error capturing heap dump: {0}

Category:
DiagnosticsWatch

Cause:
An unexpected error occurred while capturing a heap dump.

Action:
Check the exception message in the server logs, contact Oracle Support if the issue can not be corrected.

BEA-320236
Thread dump action {0} canceled

Category:
DiagnosticsWatch

Cause:
Thread dump action was cancelled.

Action:
No action necessary.

BEA-320237
Older dump file {0} removed to make space for new dump file.

Category:
DiagnosticsWatch

Cause:
Limit for number of heap or thread dump files is already reached. Removing older dump files to make space for new dump file.

Action:
No action necessary.

BEA-320238
Unable to execute scale down action {0}, cluster {1} is already at the minimum number of required running servers: {2}.

Category:
DiagnosticsWatch

Cause:

Action:

BEA-320239
Unable to execute scale up action {0}, cluster {1} is already at the maximum allowed number of running servers: {2}.

Category:
DiagnosticsWatch

Cause:

Action:

BEA-320300
The WLS ServerRuntime MBeanServer was not available for harvesting; custom MBean harvesting will not be available.

Category:
DiagnosticsHarvester

Cause:
This could be the result of a serious error in the OA&M infrastructure. Check for other error messages in the log in that area.

Action:
Contact My Oracle Support.

BEA-320301
The WLDF Harvester could not activate the Watch and Notifications framework due to an exception: {0}

Category:
DiagnosticsHarvester

Cause:
During server startup, the Watch and Notifications activation is deferred until the WLDF Harvester is fully activated. The deferred activation encountered an unexpected exception, potentially impairing the Watch and Notifications functionality.

Action:
Contact My Oracle Support.

BEA-320303
The namespace {1} for the harvested type specification {0} can not be serviced by a Managed Server instance; it is valid only when targed to an Administration Server.

Category:
DiagnosticsHarvester

Cause:
A harvested type specifying the DomainRuntime namespace was targeted to a Managed Server. A Managed Server can only service the ServerRuntime namespace.

Action:
Correct the namespace declaration of the harvested type, or retarget the WLDF configuration to an Administration Server in order to service this type.

BEA-320304
The following errors were reported during the validation of the metrics for watched values {0}: {1}

Category:
DiagnosticsHarvester

Cause:
Some of the configured harvested types may have errors, resulting in the harvester being unable to process them for collection.

Action:
Correct any issues with the harvested type configuration.

BEA-320305
The instance name {0} is not a valid ObjectName or instance name pattern.

Category:
DiagnosticsHarvester

Cause:
The instance name must be a valid JMX ObjectName, or a pattern conforming to the syntax supported by the WebLogic Diagnostics Framework.

Action:
Correct the instance name in the harvested type.

BEA-320400
The log file {0} will be rotated. Reopen the log file if tailing has stopped. This can happen on some platforms, such as Windows.

Category:
LoggingService

Cause:
This event happens whenever the log file is about to be rotated based on either size or time rotation criterion.

Action:
On certain platforms, if some application is tailing the log, the rotation fails. Stop the application tailing and reopen the tail after the rotation is complete.

BEA-320401
The log file has been rotated to {1}. Log messages will continue to be logged in {0}.

Category:
LoggingService

Cause:
This event happens after the log file is rotated based on either size or time rotation criterion.

Action:
No action is required.

BEA-320450
The DebugScope name {0} is not valid.

Category:
DebugModule

Cause:
The DebugScope with the given name is not defined in the ServerDebugMBean interface.

Action:
Configure the debug scope with a valid name.

BEA-320451
An error occurred while applying the DebugScopes configuration.

Category:
DebugModule

Cause:
This may be due to an I/O error while reading the DebugScopes from the disk.

Action:
Take action based on the error stack trace.

BEA-320452
An error occurred while adding PropertyChangeListener to bean {0}.

Category:
DebugModule

Cause:
The debug configuration bean does not support PropertyChangeListeners.

Action:
Take action based on the error stack trace.

BEA-320453
An error occurred while removing PropertyChangeListener from bean {0}.

Category:
DebugModule

Cause:
The debug configuration bean does not support PropertyChangeListeners.

Action:
Take action based on the error stack trace.

BEA-320454
An error occurred while initializing Server Debug from older DebugCategory mappings.

Category:
DebugModule

Cause:
The error details are included in the stack trace of the Exception reported.

Action:
Take action based on the error stack trace.

BEA-320500
The built-in WebLogic Diagnostics Framework resource descriptor ${0} for the selected level "{1}" could not be found; setting built-in resource to ${2}.

Category:
DiagnosticsRuntimeControl

Cause:
The WebLogic Diagnostics Framework resource descriptor for the desired built-in monitoring state could not be loaded due to either an issue with the WebLogic Server kit installation or an environmental issue in the domain configuration.

Action:
Contact My Oracle Support.

BEA-320800
Failed to cache the instrumentation engine configuration at {0} with exception {1}

Category:
DiagnosticsInstrumentor

Cause:
The destination file may not be writable or some other I/O error occurred.

Action:
Check to see if the destination file is writable.

BEA-320801
Failed to load instrumentation engine configuration {0}.

Category:
DiagnosticsInstrumentor

Cause:
The instrumentation engine configuraion may be missing or corrupt.

Action:
Contact My Oracle Support.

BEA-320802
Missing the name attribute for the instrumentation engine configuration at {0}.

Category:
DiagnosticsInstrumentor

Cause:
The engine configuration does not have the required name attribute.

Action:
Contact My Oracle Support.

BEA-320803
Duplicate instrumentation engine configuration {0} found.

Category:
DiagnosticsInstrumentor

Cause:
A duplicate instrumentation engine configuration was found.

Action:
Contact My Oracle Support.

BEA-320804
Invalid parent "{1}" for instrumentation engine configuration "{0}".

Category:
DiagnosticsInstrumentor

Cause:
The instrumentation engine configuration has an incorrect parent configuration.

Action:
Contact My Oracle Support.

BEA-320805
Required root instrumentation engine configuration was not found.

Category:
DiagnosticsInstrumentor

Cause:
The required root instrumentation engine configuration was not found.

Action:
Contact My Oracle Support.

BEA-320806
Found circular dependency with instrumentation engine configurations: {0}

Category:
DiagnosticsInstrumentor

Cause:
The instrumentation engine configurations are invalid.

Action:
Contact My Oracle Support.

BEA-320807
Parent "{0}" for instrumentation engine configurations {1}.

Category:
DiagnosticsInstrumentor

Cause:
The parent configuration for an instrumentation engine configuration cannot be located.

Action:
Contact My Oracle Support.

BEA-320900
Agent will be unable to proxy for the agents specified due to Proxy initialization error.

Category:
SNMP

Cause:
Refer to exception message for cause of initialization failure.

Action:
Take appropriate action based upon the specified exception message.

BEA-320913
Failed to register Attribute Change listener {0} for MBean type {1} on server {2}.

Category:
SNMP

Cause:
This may be due to a misconfigured SNMPAttributeChange entry specification in config.xml. Please refer to the exception message for more specific cause information.

Action:
Modify configuration of the SNMPAttributeChange entry or take appropriate action based upon the specific exception message.

BEA-320918
Failed to add NotificationListener to logBroadcaster for SNMPLogFilter {0}.

Category:
SNMP

Cause:
Please refer to the exception message for more specific cause information.

Action:
Take appropriate action based upon the specific exception message.

BEA-320923
Error creating JMX Monitor {0} of type {1} for MBean {2}.

Category:
SNMP

Cause:
This may be due to a misconfigured Monitor entry specification. Please refer to the exception message for more specific cause information.

Action:
Modify the configuration of the SNMPJMXMonitorMBean entry or take appropriate action based upon the specific exception message.

BEA-320925
Failed to send Monitor trap for server {0} for type {1} for object {2}.

Category:
SNMP

Cause:
Please refer to the exception message for more specific cause information.

Action:
Take appropriate action based upon the specific exception message.

BEA-320927
SNMP agent is initializing.

Category:
SNMP

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320928
SNMP Agent initialization failed while accessing server information for the configured Domain.

Category:
SNMP

Cause:
Refer to earlier SNMP error log information for specific information on the cause of the problem.

Action:
Take appropriate action based upon the specific exception message.

BEA-320929
SNMP agent initialization completed successfully.

Category:
SNMP

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320930
SNMP Agent Generic coldStart trap sent.

Category:
SNMP

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320931
The SNMP trap version is {0}.

Category:
SNMP

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320937
Exception occurred sending SNMP message, {0}.

Category:
SNMP

Cause:
This is an internal WebLogic Server error that occurred during the sending of an SNMP message using the TCP transport provider.

Action:
Contact My Oracle Support.

BEA-320938
SNMP Agent does not support setting values for MBean attributes through SNMP.

Category:
SNMP

Cause:
You attempted to set an MBean attribute using SNMP.

Action:
Use JMX APIs to update the WLS configuration MBeans.

BEA-320939
An error occurred while adding a row to the SNMP table for MBean {1} of type {0}.

Category:
SNMP

Cause:
This could be due to a row already existing in the SNMP Agent for the MBean or an error condition in the SNMP Agent.

Action:
Take appropriate action based on additional information in the error stack trace.

BEA-320940
An error occurred while deleting the row from the SNMP table for MBean {0}.

Category:
SNMP

Cause:
The specified MBean instance was not registered in SNMP or it could be due to an error condition in the SNMP Agent.

Action:
Take appropriate action based on additional information in the error stack trace.

BEA-320941
An SNMP message was received over the default channel instead of the dedicated SNMP channel.

Category:
SNMP

Cause:
This occurs when a dedicated Network Access Point for SNMP traffic has been configured and activated and an SNMP request is received over the default server channel.

Action:
Direct the SNMP request to the configured channel.

BEA-320942
The specified type name {0} is invalid.

Category:
SNMP

Cause:
The specified name is not recognized as a valid WebLogic Server MBean type.

Action:
Please specify the correct name for a WebLogic Server Configuration or Runtime MBean type.

BEA-320943
The specified attribute name {1} is not valid for the given type {0}.

Category:
SNMP

Cause:
The specified attribute name that is not valid was specified as part of the configuration.

Action:
Please specify the correct attribute name for the WebLogic Server Configuration or Runtime MBean type.

BEA-320944
The SecurityName attribute is not specified for the SNMPTrapDestination {0}.

Category:
SNMP

Cause:
The SNMP Agent's trap version is set to V3 and the SecurityName is not specified for the given SNMPTrapDestination.

Action:
Please specify the SecurityName attribute for which the SNMP Agent will issue V3 traps.

BEA-320945
The SNMP Agent"s TrapVersion needs to be V2 or higher to be able to send INFORM notifications.

Category:
SNMP

Cause:
The SNMPAgentMBean's SNMPTrapVersion attribute is set to V1.

Action:
Set the SNMPTrapVersion to V2 or higher in the configuration.

BEA-320946
The SNMP Agent {0} is already deployed to server {1}.

Category:
SNMP

Cause:
An attempt was made to target multiple SNMPAgentDeploymentMBeans to the same WebLogic Server instance.

Action:
Ensure that only one SNMPAgentDeploymentMBean is targeted to any Server in the domain.

BEA-320947
The AuthenticationProtocol for SNMP Agent {0} cannot be noAuth when PrivacyProtocol {1} is specified.

Category:
SNMP

Cause:
An invalid combination of authentication and privacy protocols was configured.

Action:
Specify either MD5 or DES as the AuthenticationProtocol in combination with Privacy.

BEA-320948
The SNMPTrapDestinationMBean {0} has a higher SecurityLevel {1} than the SNMPAgent''s SecurityLevel {2}.

Category:
SNMP

Cause:
An invalid combination of authentication and privacy protocols on the SNMPAgentMBean and security level on the SNMPTrapDestinationMBean has been configured.

Action:
Specify the valid security level for the users and the trap destinations.

BEA-320949
SNMPAgent {0} is configured with a security level of {1}; the security level of {3} for proxy {2} must not exceed that of the SNMP agent.

Category:
SNMP

Cause:
A security level on the SNMP proxy was configured that exceeds the security level of the SNMP agent that corresponds to its configured authentication and privacy protocols.

Action:
Configure a level of security on the proxy that is lower than the security level of the SNMP agent. For example, if the SNMP agent is configured with authentication but no privacy, configure the security level of NOAUTH_NOPRIV or AUTH_NOPRIV on the proxy.

BEA-320950
Failed to start the SNMP agent. If it failed to bind to the port, check if the port is available or the process has permission to bind to the port.

Category:
SNMP

Cause:
Binding to specified UDP and agentX ports is a common problem. The ports to which the agent binds may not be available. Also, on UNIX platforms, ports up to 1023 are protected and can be bound only by processes owned by root.

Action:
Check whether the specified ports are available. On UNIX, the default UDP port (161) and master AgentX port (705) are protected to be used by processes owned by root. In that case, either start the server as root, or configure the SNMP agent to use port numbers higher than 1023.

BEA-320951
Failed to initalize the SNMP AgentX master subagent. One possible cause is the failure to bind the Master agentX port. If this is the case, check to see if the specified AgentX port is available, or ensure that the process has permissions to bind to the desired port.

Category:
SNMP

Cause:
A common problem is with binding to the specified agentX port. The port to which the agent binds may not be available. Also, on UNIX platforms, ports up to 1023 are protected and can be bound only by processes owned by root.

Action:
Check whether the specified port is available. On UNIX, the default master AgentX port (705) is protected to be used by processes owned by root. In that case, either start the server as root, or configure the SNMP agent to use port numbers higher than 1023.

BEA-320952
Failed to send the SNMP trap or inform notification for trap OID {2}. Number of send attempts = {0}. Number of errors encountered = {1}. The detailed error message from the SNMP toolkit is {3}.

Category:
SNMP

Cause:
The SNMPTrapDestination(s) could be incorrectly configured or the SNMP Manager might not be running at the configured location.

Action:
Ensure that the SNMP Manager is available at the configured SNMP TrapDestinations.

BEA-320953
The SNMP Agent has been started on port {0}.

Category:
SNMP

Cause:
The SNMP Agent tries to bind to the configured port. If this port is not available due to another SNMP Agent being deployed to the same machine on another WebLogic Server instance then the SNMP Agent tries to find the nearest port and binds to it.

Action:
No action is needed. The port number is also reflected in the UDPListenPort attribute of the SNMPAgentRuntimeMBean interface on this Server.

BEA-320954
The SNMP Agent encountered an error while discovering Extensions {0}.

Category:
SNMP

Cause:
The SNMPAgent Extension provider implementations could not be loaded successfully.

Action:
Take corrective action based on the exception details.

BEA-320955
SNMP agent has been shut down.

Category:
SNMP

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-320956
Error registering trap destination {0} for address {1}:{2}.

Category:
SNMP

Cause:
The host name specified in the SNMPTrapDestination configuraiton is not valid.

Action:
Correct the configuration and start the SNMP agent again.

BEA-320957
Community prefix value cannot be empty or "public" or "private"

Category:
SNMP

Cause:
The SNMP agent is enabled and the community prefix attribute is empty or set to either public or private.

Action:
Correct the configuration and start the SNMP agent again.

BEA-340450
Descriptor {1} has no configuration-support in the weblogic-extension.xml file for application module {0}. JSR-88 updates will not be supported.

Category:
CustomModule

Cause:
The configuration-support stanza was missing or has XML errors.

Action:
Correct the weblogic-extension.xml file and redeploy the application.

BEA-340451
URI mismatch for base-URI ({2}) in the weblogic-extension.xml file for descriptor {1} in module {0}. Unpredictable results from JSR-88 updates are likely.

Category:
CustomModule

Cause:
The custom-module URI does not match the configuration-support base-URI.

Action:
Correct the base-URI in the configuration-support stanza of the weblogic-extension.xml file to match the custom-module URI and redeploy the application.

BEA-340452
Prepare to deploy descriptor {1} in application module {0}.

Category:
CustomModule

Cause:
This is normal behavior.

Action:
No action is required.

BEA-340454
Prepare update for descriptor {1} in application module {0}.

Category:
CustomModule

Cause:
This is normal behavior.

Action:
No action is required.

BEA-400000
Initializing message interception service.

Category:
messaging.interception

Cause:
WebLogic Server starts the message interception service.

Action:
No action is required.

BEA-400200
Incorrect arguments. Expects 2 arguments.

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400201
Migrating old security provider JARS from {0}

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400204
No security provider JARs have been upgraded.

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400205
Copying the upgraded security provider JAR to {0}

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400206
Completed upgrading of {0} old security provider JARs.

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400207
Skipped converting {0} since it is a security provider JAR built with 9.0.

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400208
No MDFs (.xmls) found in the old security provider JAR with name {0}

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400209
Created new security provider JAR {0} from {1}

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400210
The XML file {0} is not a valid MDF, hence the upgrade tool will ignore this file.

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400211
Not upgrading {0} because either this is an out-of-the-box Oracle security provider JAR or this security provider JAR is already upgraded or this is not a valid archive file (may not be a .jar).

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400212
Now processing {0}

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400213
Could not convert from MDF {0}. This file may not be a valid MDF file; verify.

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400214
Running the first phase of Security Provider Upgrade process on {0}

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-400215
First phase successful, now running the second and last phase of security provider upgrade process on {0}

Category:
Upgrade-SecurityProviders

Cause:
See the message body.

Action:
No action required.

BEA-420000
The message interception service cannot bind "{0}" to the local JNDI.

Category:
MIExceptions

Cause:
The JNDI name was already used.

Action:
Avoid using JNDI names starting with weblogic. Correct this problem then try again.

BEA-420002
The addAssociation method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of the addAssociation API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420003
The addAssociation method encounters some usage error due to "{0}".

Category:
MIExceptions

Cause:
The interception point type is unknown either due to typo or the registerInterceptionPointNameDescription method didn't register the expected interception point type first.

Action:
If this is caused by an external application then fix the related code. Otherwise, contact the customer support.

BEA-420004
The removeAssociation method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of the removeAssociation API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420005
The registerInterceptionPointNameDescription method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an llegal usage of the registerInterceptionPointNameDescription API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420006
The registerInterceptionPoint method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of the registerInterceptionPoint API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420007
The registerInterceptionPoint method encountered a usage error due to "{0}".

Category:
MIExceptions

Cause:
The interception point type is unknown either due to a typo or the registerInterceptionPointNameDescription method did not register the expected interception point type first.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420008
The unRegisterInterceptionPoint method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of the unRegisterInterceptionPoint API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420009
The registerProcessorType method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of the registerProcessorType API.

Action:
If this is caused by an external application, then fix the related code; Otherwise, contact My Oracle Support.

BEA-420010
The addProcessor method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of the addProcessor API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420011
The addProcessor method encountered a usage error due to "{0}".

Category:
MIExceptions

Cause:
The processor type is unknown either due to a typo or the registerProcessorType method did not register the expected processor type first.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420012
The removeProcessor method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of the removeProcessor API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420013
The getAssociationHandle method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of getAssociationHandle API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420014
The getProcessorHandles method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of the getProcessorHandles API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420015
The getProcessorHandle method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of the getProcessorHandle API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420016
The registerInterceptionPointNameDescriptionListener method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of the registerInterceptionPointNameDescriptionListener API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420017
The removeAssociation method encountered an input error due to "{0}".

Category:
MIExceptions

Cause:
There was an illegal usage of the removeAssociation API.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420019
The process method encountered a usage error due to "{0}".

Category:
MIExceptions

Cause:
The required processor for the given association was not created at the time. To send a message to a target that has the given association defined, the processor specified in the association needs to be added beforehand.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420020
The process method encountered a usage error due to "{0}".

Category:
MIExceptions

Cause:
The processor generated an illegal error.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420021
The process method encountered a usage error due to "{0}".

Category:
MIExceptions

Cause:
The processor generated an illegal runtime exception.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420025
The addAssociation method encountered a usage error due to "{0}".

Category:
MIExceptions

Cause:
The added association already exists.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420026
The unregisterInterceptionPoint method encountered a usage error due to "{0}".

Category:
MIExceptions

Cause:
The interception point has already been removed.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420027
The interception point name argument is invalid due to "{0}".

Category:
MIExceptions

Cause:
The interception point name argument is invalid for several possible reasons. For example, the total number of name element differs from what is being registered with the interception service or one name element is invalid by itself.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420028
The removeProcessor method encountered a usage error due to "{0}".

Category:
MIExceptions

Cause:
The processor has been removed.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420029
The registerProcessorType method encountered a usage error due to "{0}".

Category:
MIExceptions

Cause:
The processor factory class cannot be instantiated.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420030
The registerProcessorType method encountered a usage error due to "{0}".

Category:
MIExceptions

Cause:
The processor factory class cannot be instantiated.

Action:
If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

BEA-420031
The process method encountered a usage error due to "{0}".

Category:
MIExceptions

Cause:
The processor is currently processing more intercepted messages than that the association's depth allows.

Action:
Increase the depth on the association using the association handle object.

BEA-2004000
An error occurred while loading the Kodo-Oracle message dictionary.

Category:
Kodo Integration

Cause:
This can happen if the Kodo-Oracle message dictionary is not available. This dictionary should be located at {0}.

Action:
Contact My Oracle Support.

BEA-2004001
The Kodo-Oracle message dictionary was not found.

Category:
Kodo Integration

Cause:
This can happen if the Kodo-Oracle message dictionary is not available. This dictionary should be located at {0}.

Action:
Contact My Oracle Support.

BEA-2004003
Kodo localization key {0} has already been registered in the Kodo-Oracle message ID dictionary. Original value: {1}. New value: {2}. New definition from URL: {3}. The original value will be used.

Category:
Kodo Integration

Cause:
See the message body.

Action:
No action required.

BEA-2011000
The bundle {0} has started successfully.

Category:
HarvesterAPI

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2011099
The bundle {0} has been successfully stopped.

Category:
HarvesterAPI

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2011100
The bundle {0} has successfully started.

Category:
HarvesterJMX

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2011101
An unexpected Exception occurred in harvester {0}. Logging it here and continuing processing... Context: {1}, Exception: {2}

Category:
HarvesterJMX

Cause:
An unexpected exception occurred during the harvesting process.

Action:
You should attempt to uncover the reason for the underlying Exception.

BEA-2011102
An unexpected condition was encountered in harvester {0}. Logging it here and continuing processing... Context: {1}

Category:
HarvesterJMX

Cause:
An unexpected condition occurred during the harvesting process.

Action:
The user should attempt to uncover the reason for the problem.

BEA-2011103
Service with name: {0} has been prepared.

Category:
HarvesterJMX

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2011104
Service with name: {0} has been acivated.

Category:
HarvesterJMX

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2011105
Service with name: {0} has been deactivated.

Category:
HarvesterJMX

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2011199
The bundle {0} has successfully been stopped.

Category:
HarvesterJMX

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2011300
The bundle {0} has successfully started.

Category:
HarvesterUtils

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2011399
The bundle {0} has successfully been stopped.

Category:
HarvesterUtils

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2012300
The bundle {0} has successfully started.

Category:
MBeanTypingUtil

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2012301
Processing {0} MBeans.

Category:
MBeanTypingUtil

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2012302
Processed {1} MBeans for MBean utility {0}.

Category:
MBeanTypingUtil

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2012303
The MBeanTypeUtil cannot process an MBean instance due to excp {0} on MBeanServer: {1} and MBean: {2} stack trace: {3} --- Retrying once...

Category:
MBeanTypingUtil

Cause:
The MBeanTypeUtil has failed while trying to access a registered MBean.

Action:
Check for other log messages that give more information about the failure.

BEA-2012304
The MBeanTypeUtil failed for a second time to process an MBean instance due to excp: {0} on MBeanServer: {1} and MBean: {2} stack trace: {3} --- Skipping this MBean...

Category:
MBeanTypingUtil

Cause:
The MBeanTypeUtil has failed to access a registered MBean in two tries.

Action:
Check for other log messages that give more information about the failure.

BEA-2012305
The MBeanTypeUtil failed to process two distinct MBeans in a row. The most recent problem was on MBeanServer: {0} and MBean: {1} stack trace: {2} --- No further MBeans will be processed.

Category:
MBeanTypingUtil

Cause:
The MBeanTypeUtil has failed to access two consecutive different MBeans.

Action:
Check for other log messages that give more information about the failure.

BEA-2012306
{1} Unable to process the {2} of MBean: {0} . The managed process might be shutting down. Stack trace: {3}

Category:
MBeanTypingUtil

Cause:
The process is most likely shutting down, so it is safe to ignore this.

Action:
If the process is known to be active, contact My Oracle Support to determine why the MBean cannot be processed. Setting the module debug flag will cause stack traces to be printed.

BEA-2012307
{1} Unable to process the {2} of MBean: {0} . The managed process appears to be shutting down. Stack trace: {3}

Category:
MBeanTypingUtil

Cause:
The process is most likely shutting down, so it is safe to ignore this.

Action:
If the process is known to be active, contact My Oracle Support to determine why the MBean cannot be processed. Setting the module debug flag will cause stack traces to be printed.

BEA-2012308
An uexpected error occurred while scheduling work for MBeanTypeUtil instance {0} with work manager {1}: {2}

Category:
MBeanTypingUtil

Cause:
Possibly no work manager was set, or the work manager was unable to queue the request.

Action:
If the problem persists, contact My Oracle Support.

BEA-2012309
An uexpected error occurred while communicating with the MBeanServer: {0}

Category:
MBeanTypingUtil

Cause:
The MBeanServer or host process may no longer be available. If the MBeanServer is remote, there may be network issues.

Action:
If the problem persists, contact My Oracle Support.

BEA-2012399
The bundle {0} has been successfully stopped.

Category:
MBeanTypingUtil

Cause:
This is a normal operation.

Action:
No action is required.

BEA-2145000
Unable to fire asynchronous listeners. Associated stack trace follows:

Category:
BEA Cache

Cause:
An error condition was reported.

Action:
Check the Work Manager configuration for work scheduling problems.

BEA-2145001
Could not configure cache with write policy of {0} because no store has been configured for the cache.

Category:
BEA Cache

Cause:
The configuration is invalid.

Action:
Either remove the write policy configuration or specify a custom store along with it.

BEA-2150001
Validation of weblogic-pubsub.xml descriptor file failed. The error is {0}

Category:
HTTP Pubsub Server

Cause:
There are errors in the weblogic-pubsub.xml descriptor file.

Action:
Correct the error in weblogic-pubsub.xml according to the schema.

BEA-2150002
No permission on channel operation: User {0} has no permission to create channel {1}

Category:
HTTP Pubsub Server

Cause:
There are not sufficient privileges to create a channel.

Action:
Check the PubSub server configuration security settings.

BEA-2150003
No permission on channel operation: User {0} has no permission to delete channel {1}

Category:
HTTP Pubsub Server

Cause:
There are not sufficient privileges to delete a channel.

Action:
Check the PubSub server configuration security settings.

BEA-2150005
Invalid persistent-client-timeout-secs: {0}.

Category:
HTTP Pubsub Server

Cause:
The persistent-client-timeout-secs must be greater than the timeout-secs.

Action:
Check the persistent-client-timeout in the PubSub server configuration

BEA-2150006
Invalid transport type: {0}

Category:
HTTP Pubsub Server

Cause:
An invalid transport type was configured in the PubSub server configuration.

Action:
Check the PubSub server configuration.

BEA-2150007
Cannot find configuration for referenced message filter {0}; check message-filter in the PubSub server configuration.

Category:
HTTP Pubsub Server

Cause:
There is a mismatch between the message filter name referenced in the channel setting and the message-filter setting.

Action:
Check the PubSub server configuration.

BEA-2150008
There is no message filter configured in the PubSub server configuration, but there is a message filter named {0} referenced in the channel setting.

Category:
HTTP Pubsub Server

Cause:
The channel setting is requesting a message filter but the message filter was not specified in the PubSub server.

Action:
Either specify the message-filter setting or remove the message-filter reference from the channel setting.

BEA-2150009
Invalid message-filter configured: message-filter {0} is configured in PubSub server configuration, but its associated class {1} cannot be initialized correctly.

Category:
HTTP Pubsub Server

Cause:
Class {1} associated with message filter {0} is incorrect.

Action:
Check the message-filter-name and message-filter-class in the PubSub server configuration.

BEA-2150011
Action {1} on channel {0} is not allowed for any client.

Category:
HTTP Pubsub Server

Cause:
The PubSub server configuration constraints do not allow this action on this channel. This is an informational message.

Action:
No action is required.

BEA-2150012
Client {0} is an anonymous user but channel {1} requests login.

Category:
HTTP Pubsub Server

Cause:
Login is requested to perform this action. This is an informational message.

Action:
No action is required.

BEA-2150013
Client {0} is not allowed to perform action {2} on channel {1}.

Category:
HTTP Pubsub Server

Cause:
The PubSub server configuration does not allow this action on this channel. This is an informational message.

Action:
No action is required.

BEA-2150014
Client {0} is allowed to perform action {2} on channel {1}

Category:
HTTP Pubsub Server

Cause:
The PubSub server configuration is allowing this action to be performed on this channel. This is an informational message.

Action:
No action is required.

BEA-2150015
Client {0} has no permission to subscribe channel {1}

Category:
HTTP Pubsub Server

Cause:
Client {0} has no permission to subscribe channel {1}, either because the client configuration does not allow the client to access the channel, or the client is anonymous and the channel configuration only allows specific clients to access the channel.

Action:
Check the PubSub server security constraint configuration.

BEA-2150016
Client {0} has no permission to publish on channel {1}

Category:
HTTP Pubsub Server

Cause:
The client is not configured to publish on the channel or the client is anonymous and the channel is configured to only allow access to specific clients.

Action:
Check the PubSub server security constraint configuration.

BEA-2150017
Failed to register MBean for Channel {0}

Category:
HTTP Pubsub Server

Cause:
An exception occurred while registering the ChannelRuntimeMBean.

Action:
Check the stack trace for more detailed information.

BEA-2150018
Failed to unregister MBean for Channel {0}

Category:
HTTP Pubsub Server

Cause:
An exception occurred while unregistering the ChannelRuntimeMBean.

Action:
Check the stack trace for more detailed information.

BEA-2150019
Initialize PubSub server {0}

Category:
HTTP Pubsub Server

Cause:
This is an informational message.

Action:
No action is required.

BEA-2150020
Duplicate initialize PubSub server {0}

Category:
HTTP Pubsub Server

Cause:
There are multiple servlet and servlet-mapping definitions for com.bea.httppubsub.servlet.ControllerServlet in the web.xml file.

Action:
Check the web.xml file.

BEA-2150021
Cannot initialize service channel {0}

Category:
HTTP Pubsub Server

Cause:
An exception occurred when initializing the service channel.

Action:
Check the PubSub server configuration.

BEA-2150024
Unknown meta channel found from Bayeux message: {0}

Category:
HTTP Pubsub Server

Cause:
An incoming message specifies a channel other than /meta/handshake, /meta/connect, /meta/reconnect, /meta/disconnect, /meta/subscribe, or /meta/unsubscribe.

Action:
Check the Bayeux client and the incoming Bayeux message.

BEA-2150025
System property {0} is not set to specify an MBeanManagerFactory implementation.

Category:
HTTP Pubsub Server

Cause:
System property {0} is not set.

Action:
Ensure that runtime MBeans are not necessary; otherwise, set system property {0} to a proper implementation of MBeanManagerFactory.

BEA-2150026
Can not initialize instance of MBeanManagerFactory with class {0}

Category:
HTTP Pubsub Server

Cause:
An exception occurred while initializing MBeanManagerFactory.

Action:
Check the stack trace for more detailed information.

BEA-2150027
Failed to register WebPubSubRuntimeMBean for PubSub server; the ContextPath is {0}

Category:
HTTP Pubsub Server

Cause:
An exception occurred while registering WebPubSubRuntimeMBean.

Action:
Check the stack trace for more detailed information.

BEA-2150028
Failed to unregister WebPubSubRuntimeMBean for PubSub server; the ContextPath is {0}

Category:
HTTP Pubsub Server

Cause:
An exception occurred while unregistering WebPubSubRuntimeMBean.

Action:
Check the stack trace for more detailed information.

BEA-2150029
ControllerServlet initialization failed: {0}

Category:
HTTP Pubsub Server

Cause:
An exception occurred when ControllerServlet was initialized.

Action:
Check the exception stack trace for details.

BEA-2150030
Cannot fetch JSON message from incoming request

Category:
HTTP Pubsub Server

Cause:
For long-polling request messages, messages are sent to the server as the body of a POST, encoded either as "application/x-www-form-urlencoded" or as "text/json". If sent as form encoded, the Bayeux messages are sent as the "message" parameter. For callback-polling request messages, messages are sent to the server either using POST requests as per long-polling transport or as the "message" URL parameter of a GET request.

Action:
Check the incoming HTTP request and the Bayeux protocol specification.

BEA-2150031
Cannot load properties from {0} in classpath.

Category:
HTTP Pubsub Server

Cause:
The property file does not exist in the classpath.

Action:
Check the classpath.

BEA-2150032
Cannot find persistent store {0} specified to channel {1}; will use the default store.

Category:
HTTP Pubsub Server

Cause:
The persistent store may not be configured properly.

Action:
Check the configuration of the persistent store.

BEA-2150033
Invalid client-timeout-secs: {0}.

Category:
HTTP Pubsub Server

Cause:
Either a negative or a zero value was set for client-timeout-secs.

Action:
Check the PubSub server configuration.

BEA-2150034
Invalid interval-millisecs: {0}.

Category:
HTTP Pubsub Server

Cause:
A negative value was set for interval-millisecs.

Action:
Check the PubSub server configuration.

BEA-2150035
Invalid multi-frame-interval-millisecs: {0}.

Category:
HTTP Pubsub Server

Cause:
A negative value wass set for multi-frame-interval-millisecs.

Action:
Check tue PubSub server configuration.

BEA-2150036
Invalid persistent-client-timeout-secs: {0}.

Category:
HTTP Pubsub Server

Cause:
Either a negative value or zero was set for persistent-client-timeout-secs.

Action:
Check the PubSub server configuration.

BEA-2150037
Invalid max-persistent-message-duration-secs: {0}.

Category:
HTTP Pubsub Server

Cause:
Either a negative value or zero was set for max-persistent-message-duration-secs.

Action:
Check the PubSub server configuration.

BEA-2150038
Initializing channel authorization manager: {0}

Category:
HTTP Pubsub Server

Cause:
This channel authorization manager will be used for authorizing channel actions.

Action:
No action is required.

BEA-2150039
Error initializing channel authorization manager.

Category:
HTTP Pubsub Server

Cause:
The initialization of channel authorization manager failed.

Action:
See the exception stack trace for details.

BEA-2150041
Invalid channel {0}, cause is {1}.

Category:
HTTP Pubsub Server

Cause:
An invalid channel field was found.

Action:
Check the Bayeux client.

BEA-2150042
A role {0} is being deployed implicitly without a pricipal mapping in the corresponding weblogic.xml.

Category:
HTTP Pubsub Server

Cause:
There is no security-role-assignment for role {0}

Action:
Create a security-role-assignment in weblogic.xml for role {0}

BEA-2150043
Security authorization has been disabled for the PubSub server.

Category:
HTTP Pubsub Server

Cause:
PubSub server security has been disabled by an undocumented system property.

Action:
If this property has not been set deliberately, verify all the system properties that begin with com.bea.httppubsub.security.

BEA-2150044
Invalid connection-timeout-secs: {0}.

Category:
HTTP Pubsub Server

Cause:
Either a negative or a zero value was set for connection-timeout-secs.

Action:
Check the PubSub server configuration.

BEA-2150045
Incoming Bayeux message does not contain 'channel' field.

Category:
HTTP Pubsub Server

Cause:
Incoming Bayeux message did not contain the 'channel' field.

Action:
Turn on Bayeux message debug flag to check the Bayeux message sent by the client.

BEA-2150046
Invalid JSON format of a Bayeux message

Category:
HTTP Pubsub Server

Cause:
A Bayeux message could not be recognized by the JSON parser.

Action:
Turn on the Bayeux message debug flag to check the Bayeux message and exception for details.

BEA-2154000
Enabling FastSwap on application "{0}".

Category:
FastSwap

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-2154001
Starting FastSwap operation on application "{0}".

Category:
FastSwap

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-2154002
Finished FastSwap operation on application "{0}" with status {1}.

Category:
FastSwap

Cause:
This message is for informational purposes only.

Action:
No action is required.

BEA-2154003
FastSwap operation on application "{0}" failed: {1}.

Category:
FastSwap

Cause:
One or more classes could not be redefined.

Action:
Redeploy the application for updates to classes to take effect.

BEA-2156001
"config-root" {0} is not a directory.

Category:
WebLogicDescriptorWL

Cause:
The "config-root" may not have been set properly.

Action:
Verify that the "config-root" is correct.

BEA-2156002
Attribute "{0}": duration value "{1}" is not valid: {2}

Category:
WebLogicDescriptorWL

Cause:
The provided duration value was not a valid duration lexical representation.

Action:
See the lexical rules for a javax.datatype.Duration, and ensure that the provided duration value is valid according to these rules.

BEA-2156003
Attribute "{0}": logical store name value "{1}" is not valid.

Category:
WebLogicDescriptorWL

Cause:
The provided logical store name value was not a valid name. Logical store names must be valid Java identifiers.

Action:
See the lexical rules for a Java identifier, and ensure that the logical store name follows these rules.

BEA-2156004
Attribute "{0}": JNDI name value "{1}" is not valid.

Category:
WebLogicDescriptorWL

Cause:
The provided JNDI name value was not a valid name. JNDI names must be non-null and non-empty and meet the rules of the J2EE platform's JNDI implementation.

Action:
See the lexical rules for a JNDI name, and ensure that the JNDI name follows these rules.

BEA-2156200
Unable to load descriptor {1} of module {0}. The error is {2}.

Category:
Munger

Cause:
The descriptor is not valid.

Action:
Correct the descriptor.

BEA-2156201
An error occurred while parsing descriptors: {0}.

Category:
Munger

Cause:
Check the stack trace.

Action:
Check the stack trace.

BEA-2156202
References were found in the deployment plan for module "{0}" with URI, "{1}". The plan was merged.

Category:
Munger

Cause:
The plan contained variable overrides.

Action:
No action is required. This is an informational message.

BEA-2156203
A version attribute was not found in element "{0}" in the deployment descriptor {1}. A version attribute is required, but this version of the WebLogic Server will assume that the latest version is used. Future versions of WebLogic Server will reject descriptors that do not specify the Java EE version. To eliminate this warning, add an appropriate "version=" to element "{0}" in the deployment descriptor.

Category:
Munger

Cause:
The required version attribute was missing.

Action:
Add the version attribute with the appropriate JEE version value.

BEA-2156204
The root element {0} is missing in the descriptor file {1}.

Category:
Munger

Cause:
The required root element was missing in the descriptor file.

Action:
Add the root element to the descriptor file.

BEA-2156205
Updating the configuration with the deployment plan overrides for module "{0}" with URI, "{1}".

Category:
Munger

Cause:
A deployment plan was specified for the application.

Action:
No action is required. This is an informational message.

BEA-2156206
No module overrides were found in the deployment plan for module "{0}" with URI, "{1}". If overrides were expected for this module, verify the deployment plan.

Category:
Munger

Cause:
The plan contained no matching variable overrides.

Action:
No action is required. This is an informational message. It may be an expected action.

BEA-2156207
The variable assignment from the deployment plan with variable name "{0}" and XPath "{1}" will be included when overriding the deployment configuration.

Category:
Munger

Cause:
The plan contained matching variable overrides.

Action:
No action is required. This is an informational message used to troubleshoot deployment plan overrides.

BEA-2156208
The variable assignment from the deployment plan with variable name "{0}" and XPath "{1}" will be included when overriding the deployment configuration.

Category:
Munger

Cause:
The plan contained matching variable overrides.

Action:
No action is required. This is an informational message used to troubleshoot deployment plan overrides.

BEA-2156209
Applying the overrides from the deployment plan for module "{0}" with URI, "{1}".

Category:
Munger

Cause:
A deployment plan was specified for the application.

Action:
No action is required. This is an informational message.

BEA-2156210
Applying the override for variable "{0}" with XPath "{1}" and operation "{2}".

Category:
Munger

Cause:
A deployment plan was specified for the application.

Action:
No action is required. This is an informational message.

BEA-2156211
After applying the overrides from the deployment plan, the descriptor "{0}" is: "{1}".

Category:
Munger

Cause:
A deployment plan was specified for the application. The descriptor was updated.

Action:
No action is required. This is an informational message.

BEA-2156212
An error occurred while parsing the specifed XPath "{0}" : {1}.

Category:
Munger

Cause:
The specified XPath value was invalid.

Action:
Check the associated exception to determine the cause, and correct the XPath value.

BEA-2156213
An error occurred while parsing the specifed XPath "{0}" : {1}.

Category:
Munger

Cause:
The specified XPath value was invalid.

Action:
Check the associated exception to determine the cause, and correct the XPath value.

BEA-2156214
The XPath "{0}" specifies a key selection but the bean "{1}" does not have any keys defined.

Category:
Munger

Cause:
The specified XPath value was invalid because no keys were defined for this element.

Action:
Check the associated schema, and ensure that the element has the corresponding key.

BEA-2156215
Removed the value matched by the deployment plan variable "{0}" with element name "{1}".

Category:
Munger

Cause:
A deployment plan was specified for the application, and an element has been removed.

Action:
No action is required. This is an informational message.

BEA-2156216
The deployment plan operation failed because there was no method named "{0}" on the bean "{1}" corresponding to the element "{2}".

Category:
Munger

Cause:
A deployment plan operation requires a corresponding destroy, remove, or set method. This method was not present.

Action:
Contact My Oracle Support.

BEA-2156217
An error occurred while performing the plan operation for variable "{0}" with element name "{1}" : {2}.

Category:
Munger

Cause:
An unexpected exception occurred during the deployment plan operation.

Action:
Check the associated exception to determine the cause, and correct the issue.

BEA-2156218
Updated the element matched by the deployment plan variable "{0}" with element name "{1}" to have value "{2}".

Category:
Munger

Cause:
A deployment plan was specified for the application, and a matching element has been updated.

Action:
No action is required. This is an informational message.

BEA-2156219
Created the element matched by the deployment plan variable "{0}" with element name "{1}".

Category:
Munger

Cause:
A deployment plan was specified for the application, and a matching element has been created.

Action:
No action is required. This is an informational message.

BEA-2156220
Created the element matched by the deployment plan variable "{0}" with element name "{1}" to have name "{2}".

Category:
Munger

Cause:
A deployment plan was specified for the application, and a matching element has been created.

Action:
No action is required. This is an informational message.

BEA-2156221
The remove operation for the deployment plan variable "{0}" with element name "{1}" specified an array index of "{2}" but the array was smaller, so no elements were removed.

Category:
Munger

Cause:
The specified array index was larger than the size of the array.

Action:
No action is required. This is an informational message.

BEA-2156222
The variable "{0}" specifies a property "{1}" that is a primitive array but no index is specified in the XPath.

Category:
Munger

Cause:
The specified XPath value was invalid since no array index was defined for this element.

Action:
Check the XPath, and specify an index.

BEA-2156223
The variable "{0}" for the add operation does not specify a property in the XPath "{1}". This variable assignment has been ignored.

Category:
Munger

Cause:
The specified XPath value was invalid since no property was specified for the add operation.

Action:
Check the XPath, and specify a property.

BEA-2156224
Added the element matched by the deployment plan variable "{0}" with element name "{1}" with value "{2}".

Category:
Munger

Cause:
A deployment plan was specified for the application, and a matching element has been added.

Action:
No action is required. This is an informational message.

BEA-2156225
The XPath "{0}" contains a trailing invalid "/". It has been ignored. Remove it from the XPath expression.

Category:
Munger

Cause:
The specified XPath value was invalid because it contained a trailing slash.

Action:
Remove the trailing slash.

BEA-2156226
Skipping the override for the deployment plan variable "{0}" and XPath "{1}" since the value is not set in the deployment plan.

Category:
Munger

Cause:
A deployment plan did not contain a value for the variable.

Action:
Add a variable value if one is desired, or remove the variable assignment if it is not needed.

BEA-2156227
The "{0}" deployment descriptor for the "{1}" module is in DTD format. Overrides from the deployment plan will NOT be applied since only deployment descriptors in XML Schema format are supported.

Category:
Munger

Cause:
A deployment descriptor in DTD format exists in the application archive.

Action:
Convert the deployment descriptor to an XML Schema format.

BEA-2156228
Updating the configuration with the resource deployment plan overrides for resource "{0}".

Category:
Munger

Cause:
A resource deployment plan was specified for the application.

Action:
No action is required. This is an informational message.

BEA-2156229
References were found in the resource deployment plan for resource "{0}". The plan was merged.

Category:
Munger

Cause:
The plan contained variable overrides.

Action:
No action is required. This is an informational message.

BEA-2156230
No resource overrides were found in the resource deployment plan for resource "{0}". If overrides were expected for this resource, verify the resource deployment plan.

Category:
Munger

Cause:
The plan contained no matching variable overrides.

Action:
No action is required. This is an informational message. It may be an expected action.

BEA-2156231
Applying the overrides from the resource deployment plan for resource "{0}".

Category:
Munger

Cause:
A resource deployment plan was specified for the application.

Action:
No action is required. This is an informational message.

BEA-2156250
The value {1} is illegal for {0}. Legal value for this attribute is >= -1. Although the current release of WebLogic Server is accepting this value, future releases may reject the configuration.

Category:
WebLogicJavaEEDescriptorValidator

Cause:
The current WebLogic Server version accepts this value to support prior releases that allowed arbitrary negative values.

Action:
Fix the configuration to specify a value for this parameter in the valid legal range.

BEA-2156300
Coherence JAR is in the system classpath and there is more than one instance of CoherenceClusterSystemResourceMBean defined using {0}

Category:
CacheProvider

Cause:
Multiple instances of CoherenceClusterSystemResourceMBean were targeted.

Action:
When the Coherence JAR is in the system classpath, only one CoherenceClusterSystemResourceMBean should be targeted to the server.

BEA-2156301
Failed to shut down application {0} due to {1}

Category:
CacheProvider

Cause:
Failed to shut down application {0} due to {1}

Action:
Examine the exception details and take corrective actions.

BEA-2156302
Only one server can be a management proxy in a Coherence cluster. {0} has {1} and {2} set as management proxies

Category:
CacheProvider

Cause:
Only one server can be a management proxy in a Coherence cluster. {0} has {1} and {2} set as management proxies.

Action:
Examine the CoherenceMemberConfig management proxy setting for each server.

BEA-2156303
Invoking {0} on node {1} resulted in {2}.

Category:
CacheProvider

Cause:
See the message body.

Action:
No action is required.

BEA-2156304
MBeanServerConnector not available at: {0}

Category:
CacheProvider

Cause:
See the message body.

Action:
No action is required.

BEA-2156400
The validation.xml file, located at {0}, does not conform to the JSR 303 specifications.

Category:
Weblogic-Validation

Cause:
The file does not conform to the JSR 303 specification. This maybe because the file is intended to configure another validation framework or because of a typo in the file.

Action:
JSR 303 specifies the location of the validator descriptor as either WEB-INF for web application or META-INF for all other cases. A validation.xml file at that location should only be used for the purpose of configuring javax.validation. If the purpose of the file is to configure another validation framework, consider using a different name or placing the file in a different location.

BEA-2156401
Invalid URL, {0}, because {1}.

Category:
Weblogic-Validation

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-2156402
Unable to process URL, {0}. Is from jar: {1} resourceDir: {2} resourcePath: {3}.

Category:
Weblogic-Validation

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-2156403
Unable to process URL, {0}, because {1}.

Category:
Weblogic-Validation

Cause:
The cause of the error is contained in the error message.

Action:
Carefully examine the error message to determine the cause of the error and determine the best way to fix it.

BEA-2156404
Unable to find a Validation Context. {0}

Category:
Weblogic-Validation

Cause:
See the message body.

Action:
Check for other log messages that give more information about the failure.

BEA-2156405
Unable to read resource, {0}, because {1}

Category:
Weblogic-Validation

Cause:
An IOException has occurred.

Action:
Insure that the resource is available for read.

BEA-2159000
An exception occurred while the listener {1} processed event {0}. The error is {1}.

Category:
InternalEventBus

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Fix the issue related to the embedded root exception. If the listener associated with the exception is an Oracle class, contact My Oracle Support.

BEA-2159001
An exception occurred while initializing WLS internal event bus {0}. The error is {1}.

Category:
InternalEventBus

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
This is an internal WebLogic Server error and should be reported as a bug to My Oracle Support.

BEA-2159002
An exception occurred while loading the listener class {0}. The error is {1}. This listener will not be registered.

Category:
InternalEventBus

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Fix the issue related to the embedded root exception. If the listener associated with the exception is an Oracle class, contact My Oracle Support.

BEA-2159003
An exception occurred while instantiating an instance of listener class {0}. The error is {1}. This listener will not be registered.

Category:
InternalEventBus

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Fix the issue related to the embedded root exception. If the listener associated with the exception is an Oracle class, contact My Oracle Support.

BEA-2159004
An exception occurred while registering listeners defined as resources. The error is {1}.

Category:
InternalEventBus

Cause:
Refer to the embedded exception information for more details as to the probable cause of this error.

Action:
Fix the issue related to the embedded root exception. If the listeners associated with the exception are Oracle listeners, contact My Oracle Support.

BEA-2159005
An error occurred while processing the WebLogic internal events "{0}". The error is {1}.

Category:
InternalEventBus

Cause:
See the embedded root exception.

Action:
Fix the issue related to the embedded root exception.

BEA-2159700
{0}

Category:
REST

Cause:
REST logs informational messages about REST usage.

Action:
No action is required.

BEA-2159701
{0}

Category:
REST

Cause:
REST has encountered an error that is potentially harmful.

Action:
Review the warning message text to determine the appropriate action.

BEA-2159702
REST encountered the following error: {0}

Category:
REST

Cause:
REST has encountered an error, but may continue to run.

Action:
Review the error message text to determine the appropriate action.

BEA-2159703
REST encountered the following error: {0}

Category:
REST

Cause:
REST has encountered a critical error.

Action:
Review the message text to determine the appropriate action.

BEA-2160000
Context "{0}" is not a web context. Spring runtime MBeans cannot be created.

Category:
WeblogicSpring

Cause:
The WeblogicSpringApplicationListener bean was added to (or registered as a listener on) an ApplicationContext that is not a web application context.

Action:
Use WeblogicSpringApplicationListener only with a WebApplicationContext.

BEA-2160001
WebAppComponentRuntimeMBean not found. Spring runtime MBeans cannot be created.

Category:
WeblogicSpring

Cause:
See the message detail.

Action:
Check for other log messages that give more information about the failure.

BEA-2160002
"{0}" is not a registered scope name.

Category:
WeblogicSpring

Cause:
The scope name supplied to a runtime mbean operation is not registered.

Action:
Supply a registered scope name to the runtime mbean operation.

BEA-2162200
No Main-Class defined in the manifest file of Java Module: {0}. This module will be treated as a utility JAR and subsequent initialization steps will be skipped.

Category:
Application Client

Cause:
See the message body.

Action:
No action is required unless you believe that this should be a Java client module. In this case, you should specify Main_Class for this module in MANIFEST.MF.

BEA-2162206
Warning: Could not find an entry for javax.transaction.UserTransaction in the root context.

Category:
Application Client

Cause:
There is no entry for javax.transaction.UserTransaction in the root context.

Action:
Contact My Oracle Support.

BEA-2162210
No persistence unit named "{0}" is available in scope.

Category:
Application Client

Cause:
See the message body.

Action:
No action is required.

BEA-2162224
No {0} was specified in your client-jar file: {1}.

Category:
Application Client

Cause:
This is a retired message.

Action:
No action is required.

BEA-2162231
Warning: Could not bind java:comp/DefaultJMSConnectionFactory due to the following exception - {0}.

Category:
Application Client

Cause:
Binding java:comp/DefaultJMSConnectionFactory to the application client container failed.

Action:
Contact My Oracle Support.

BEA-2162500
Class, {0}, was compiled with an incompatible version of Java. Ensure that all the classes needed by the application have been compiled with a compatible java version. {1}

Category:
Class Loaders

Cause:
This error occurred while attempting to use a class that was compiled with a java compiler version that is not compatible with the JVM used by the application server.

Action:
Ensure that this and other classes are compiled with a compiler that is compatible with the JVM used by the application server.

BEA-2162501
Class bytes found, but could not define class, {0} due to the following error: {1}

Category:
Class Loaders

Cause:
The cause of this is unknown.

Action:
Contact My Oracle Support for assistance.

BEA-2162502
Ignoring manifest file for classpath entry {0}.

Category:
Class Loaders

Cause:
An error occurred while reading the manifest file for the classpath entry.

Action:
Inspect the exception stack trace and correct the problem.

BEA-2162503
Not adding pre-processor class {0}.

Category:
Class Loaders

Cause:
The pre-processor class was not found.

Action:
Inspect the exception stack trace and correct the problem.

BEA-2162504
Not adding pre-processor class {0}.

Category:
Class Loaders

Cause:
The pre-processor class could not be intialized.

Action:
Inspect the exception stack trace and correct the problem.

BEA-2162505
Skipping pre-processing using pre-processor {0} with description: {1}

Category:
Class Loaders

Cause:
An error was encountered while pre-processing.

Action:
Inspect the exception stack trace and correct the problem.

BEA-2162506
Ignoring manifest during definition of class {0}.

Category:
Class Loaders

Cause:
An error occurred while reading the manifest for the jar file. The manifest declaration will be ignored during class definition.

Action:
To fix this problem, inspect the exception stack trace, and correct the problem

BEA-2162507
Aborting annotation processing due to a symlink cycle. The following directory has been visited already. Path: {0} Cannonical Path: {1}.

Category:
Class Loaders

Cause:
Symlink cycles in a classes directory tree are causing the directory traversal to repeat the traversal of part of the directory tree indefinitely.

Action:
Inspect the classes directory that is related to the reported path for symlink. Ensure that the symlinks do not cause cycling. Differences between the Path and Cannonical Path may suggest where the troublesome symlink lies.

BEA-2162508
corrupted jar found. file:{0} ,md5sum:{1}, lastModified:{2}.

Category:
Class Loaders

Cause:
An error occurred while reading jar file. This means archive corruption.

Action:
To fix this problem, inspect the exception stack trace, and correct the problem

BEA-2162600
Creating ManagedThreadFactory "{2}" (partition="{3}", module="{0}", application="{1}")

Category:
CONCURRENCY

Cause:
The application is being initialized.

Action:
No action is required.

BEA-2162601
Creating ContextService "{2}" (partition="{3}", module="{0}", application="{1}")

Category:
CONCURRENCY

Cause:
The application is being initialized.

Action:
No action is required.

BEA-2162602
{0} is still running, create another timer {1}.

Category:
CONCURRENCY

Cause:
A timer with the same name in ManagedScheduledExecutorService has already been created.

Action:
No action is required.

BEA-2162603
The value {1} of parameter {0} is illegal.

Category:
CONCURRENCY

Cause:
The provided parameter value is illegal.

Action:
Provide a valid value.

BEA-2162604
Unable to create runtime MBean for concurrent managed object {0}. {1}

Category:
CONCURRENCY

Cause:
A fatal error occurred while creating the runtime MBeans.

Action:
Contact My Oracle Support and provide them with the server logs.

BEA-2162605
ManagedThreadFactory {0} rejected newThread request as current length reached max capacity {1}, limit type {2}.

Category:
CONCURRENCY

Cause:
A newThread request was rejected as the capacity was reached.

Action:
Configure the MaxConcurrentNewThreads attribute to limit running threads created by ManagedThreadFactory.

BEA-2162606
Managed(Scheduled)ExecutorService {0} rejected newThread request as current length reached max capacity {1}, limit type {2}.

Category:
CONCURRENCY

Cause:
A newThread request was rejected as the capacity was reached.

Action:
Configure the MaxConcurrentLongRunningThreads attribute to limit running threads created by Managed(Scheduled)ExecutorService.

BEA-2162607
Out-of-date thread {1} is still running when ManagedThreadFactory {0} is restarted.

Category:
CONCURRENCY

Cause:
A thread was shut down and interrupted when the ManagedThreadFactory was stopped but it was still running when the ManagedThreadFactory was restarted.

Action:
No action is required. The thread will be still running in a shutdown and interrupted state.

BEA-2162608
ManagedTaskListener registered for task {0} throws exception in method {1}: {2}

Category:
CONCURRENCY

Cause:
A user-provided ManagedTaskListener implementation may have a defect.

Action:
Check your ManagedTaskListener implementation.

BEA-2162609
An attempt to process user a transaction failed:{0}

Category:
CONCURRENCY

Cause:
Transaction processing failed.

Action:
No action is required.

BEA-2162610
Creating ManagedExecutorService "{4}" (partition="{0}", module="{2}", application="{1}", workmanager="{3}")

Category:
CONCURRENCY

Cause:
The application is being initialized.

Action:
No action is required.

BEA-2162611
Creating ManagedScheduledExecutorService "{4}" (partition="{0}", module="{2}", application="{1}", workmanager="{3}")

Category:
CONCURRENCY

Cause:
The application is being initialized.

Action:
No action is required.

BEA-2162612
ManagedThreadFactory {0} rejected newThread request as it is in an illegal state such as stopped.

Category:
CONCURRENCY

Cause:
A newThread request was rejected with an IllegalStateException as the ManagedThreadFactory was in an illegal state such as stopped.

Action:
No action is required.

BEA-2162613
The invocation of method {0} of a proxy object failed because of the exception: {1}.

Category:
CONCURRENCY

Cause:
The invocation of method {0} of proxy object failed because of the exception: {1}.

Action:
No action is required.

BEA-2162614
Workmanager {0} in application {1} could not be found, using default.

Category:
CONCURRENCY

Cause:
The dispatch-policy attribute is not correct.

Action:
Correct the dispatch-policy attribute.

BEA-2162615
Concurrent object {2} in application {0} module {1} could not be found, using default.

Category:
CONCURRENCY

Cause:
The resource-link or mappedName attribute of the resource reference is not correct.

Action:
Correct the resource-link or mappedName attribute of the resource reference.

BEA-2162616
Proxy is created by a different ContextService object.

Category:
CONCURRENCY

Cause:
This occurred while trying to get the execution properties on a contextual object proxy that was created by a different ContextService.

Action:
No action is required.

BEA-2162617
ContextObject is not a valid contextual object proxy created with the createContextualProxy method.

Category:
CONCURRENCY

Cause:
This occurred while trying to get the execution properties on an invalid contextual object proxy by calling the getExecutionProperties() method of ContextService.

Action:
No action is required.

BEA-2162618
The instance parameter of createContextualProxy method cannot be null.

Category:
CONCURRENCY

Cause:
This occurred while trying to create a new contextual object proxy by calling the createContextualProxy method of ContextService but the input object instance was null.

Action:
No action is required.

BEA-2162619
The interfaces parameter of createContextualProxy method cannot be null.

Category:
CONCURRENCY

Cause:
This occurred while trying to create a new contextual object proxy by calling the createContextualProxy method of ContextService but no interface was specified.

Action:
No action is required.

BEA-2162620
Class does not implement at least one of the provided interfaces.

Category:
CONCURRENCY

Cause:
This occurred while trying to create a new contextual object proxy by calling the createContextualProxy method of ContextService, but the instance does not implement at least one of the provided interfaces.

Action:
No action is required.

BEA-2162621
Lifecycle related method is not supported.

Category:
CONCURRENCY

Cause:
An attempt was made to invoke an unsupported lifecycle related method.

Action:
No action is required.

BEA-2162622
Task list is empty.

Category:
CONCURRENCY

Cause:
An empty task list was passed to invokeAll/invokeAny.

Action:
No action is required.

BEA-2162623
Task submission was rejected because executor {0} has been stopped.

Category:
CONCURRENCY

Cause:
A task was submitted to a stopped executor.

Action:
No action is required.

BEA-2162624
Task was canceled because concurrent managed object {0} is stopped.

Category:
CONCURRENCY

Cause:
A task was submitted to a stopped concurrent managed object.

Action:
No action is required.

BEA-2162625
ManagedExecutorService {0} rejected a newThread request as it is in an illegal state such as stopped.

Category:
CONCURRENCY

Cause:
A newThread request was rejected with an IllegalStateException as the ManagedExecutorService was in an illegal state such as stopped.

Action:
No action is required.

BEA-2162626
Task {0} was canceled by user.

Category:
CONCURRENCY

Cause:
A task was canceled by a user.

Action:
No action is required.

BEA-2162627
Contextual object proxy deserialization error: {0} is expected but current object is {1}.

Category:
CONCURRENCY

Cause:
An attempt was made to deserialize a contextual object proxy but the context was not as expected.

Action:
No action is required.

BEA-2162628
Save contexts failed: {0}.

Category:
CONCURRENCY

Cause:
An exception occurred while saving the current contexts. The context's setup in the executing thread will be ignored.

Action:
No action is required.

BEA-2162629
Setup contexts failed: {0}.

Category:
CONCURRENCY

Cause:
An exception occurred while setting up contexts in the executing thread. The contexts will be rolled back.

Action:
No action is required.

BEA-2162630
Reset contexts failed: {0}.

Category:
CONCURRENCY

Cause:
An exception occurred while resetting the current contexts in the executing thread.

Action:
No action is required.

BEA-2162631
Concurrent managed objects are used before the concurrent service is started. {0}

Category:
CONCURRENCY

Cause:
Concurrent managed objects were used before the concurrent service was started.

Action:
No action is required.

BEA-2162632
New thread request was rejected by ManagedThreadFactory {0} because {1}.

Category:
CONCURRENCY

Cause:
A new thread request was rejected by the limit of maximum new threads or the serialize-deserialize check.

Action:
No action is required.

BEA-2162633
Contextual object proxy deserialization error: cannot get the expected {0} from cache with key {1}.

Category:
CONCURRENCY

Cause:
An attempt was made to deserialize a contextual object proxy but no related context can be found in cache. Check the status of the corresponding application to see if the context was released.

Action:
No action is required.

BEA-2162634
Override {0} is not allowed.

Category:
CONCURRENCY

Cause:
A task is canceled by a user

Action:
No action is required.

BEA-2162635
Override is is not allowed.

Category:
CONCURRENCY

Cause:
The JNDI name was not correct.

Action:
No action is required.

BEA-2162636
Task {1} submitted to {0} skip partition class loader check.

Category:
CONCURRENCY

Cause:
This is an information message.

Action:
No action is required.

BEA-2162637
Unable to create ConcurrentManagedObjectsRuntimeMBean for partition {0}. {1}

Category:
CONCURRENCY

Cause:
An exception occurred while creating the ConcurrentManagedObjectsRuntimeMBean.

Action:
Contact My Oracle Support and provide them with the server logs.

BEA-2162638
Unable to destroy ConcurrentManagedObjectsRuntimeMBean for partition {0}. {1}

Category:
CONCURRENCY

Cause:
An exception occurred while destroying the ConcurrentManagedObjectsRuntimeMBean.

Action:
Contact My Oracle Support and provide them with the server logs.

BEA-2162639
Context setup failed because {0} is not started.

Category:
CONCURRENCY

Cause:
Context setup failed because {0} is not started.

Action:
Check the state of the corresponding partition, application or module.

BEA-2162640
Unable to create the partition level concurrent manangement object.

Category:
CONCURRENCY

Cause:
The partition level concurrent manangement object could not be created.

Action:
Contact My Oracle Support and provide them with the server logs.

BEA-2162641
Trying to unbind a non-existent {0} factory named {1}: {2}

Category:
CONCURRENCY

Cause:
An attempt was made to unbind a non-existent factory.

Action:
Contact My Oracle Support and provide them with the server logs.

BEA-2162642
Roll back transaction {0} because it was begun but has not been committed by task {1}.

Category:
CONCURRENCY

Cause:
The transaction was not committed by the task after it had begun.

Action:
Contact My Oracle Support and provide them with the server logs.

BEA-2162643
Trigger used for task {0} throws exception in method {1}: {2}

Category:
CONCURRENCY

Cause:
A Trigger implementation may have a defect.

Action:
Check the Trigger implementation.

BEA-2162644
{0} belonging to ManagedExecutorService {1}, application {2} was released as the ManagedExecutorService was shutting down.

Category:
CONCURRENCY

Cause:
This is an information message.

Action:
No action is required.

BEA-2162645
{0} belonging to ManagedExecutorService {1}, WorkManager {2}, application {3} was released as the WorkManager was shutdown and the task was not submitted by an administrator.

Category:
CONCURRENCY

Cause:
This is an information message.

Action:
No action is required.

BEA-2162646
{0} cannot be used outside of its partition in {1}: {2}

Category:
CONCURRENCY

Cause:
A concurrent managed object was used outside of its partition.

Action:
Check all code that is submitting tasks to the concurrent managed object.

BEA-2162647
Application Level {0} cannot be used outside of its application in {1}: {2}

Category:
CONCURRENCY

Cause:
An application-level concurrent managed object was used outside of its application.

Action:
Check all code that is submitting tasks to the concurrent managed object.

BEA-2162648
{0} rejected the task because the submitting component {1} was not started: {2}

Category:
CONCURRENCY

Cause:
A concurrent managed object was used by another component and that component was not started.

Action:
Check the state of the submitting component.

BEA-2162649
{0} rejected createContextualProxy because it was not started.

Category:
CONCURRENCY

Cause:
createContextualProxy was rejected with an IllegalArgument exception as the ContextService was not started.

Action:
Check the state of the ContextService.

BEA-2162650
Context setup failed because the submitting component {0} is not started.

Category:
CONCURRENCY

Cause:
Context setup failed because the submitting component {0} is not started.

Action:
Check the state of the submitting component.

BEA-2162651
{0} belonging to ManagedExecutorService {1}, application {2} was released as the submitting application {3} was shutting down.

Category:
CONCURRENCY

Cause:
This is an informational message.

Action:
No action is required.

BEA-2162652
Long running task was canceled because the submitting application {0} is stopped.

Category:
CONCURRENCY

Cause:
A long running task was canceled because the submitting application {0} is stopped.

Action:
No action is required.

BEA-2162700
{0}: Cluster {1} contains {2} running Managed Servers which meets or exceeds the maximum number of allowed servers ({3}). The cluster will not be scaled up.

Category:
Elasticity

Cause:
The cluster size has already reached the configured Maximum Elastic Cluster Size.

Action:
If possible, for example, if additional capacity exists, increase the Maximum Elastic Cluster Size.

BEA-2162701
{0}: Cluster {1} contains a sufficient number of available Managed Servers. Cluster will be scaled by {2} servers.

Category:
Elasticity

Cause:
See the message body.

Action:
No action required.

BEA-2162702
{0}: Proposed size ({2}) for cluster {1} will exceed the configured maximum size. Limiting cluster size to {3}.

Category:
Elasticity

Cause:
See the message body.

Action:
No action required.

BEA-2162703
{0}: Cluster {1} will be expanded by {2} servers.

Category:
Elasticity

Cause:
See the message body.

Action:
No action required.

BEA-2162704
{0}: Cluster {1} contains only {2} running Managed Servers which is less or equal to the minimum number of servers ({3}). The cluster will not be scaled down.

Category:
Elasticity

Cause:
Cluster size has already reached the configured Minimum Elastic Cluster Size.

Action:
No action is required.

BEA-2162705
{0}: Cluster {1} will be scaled down by {2} servers.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162706
{0}: Cluster {1} has only {2} running servers. The cluster will be scaled down by {3} servers instead of the requested scaling size {4} since the minimum size of the cluster is {5}.

Category:
Elasticity

Cause:
There are fewer running servers than what may be necessary to satisfy the request to shut down the specified number of servers.

Action:
No action required.

BEA-2162707
A suitable Lifecycle Management end point was not found while performing a scaling operation on cluster {0}. The scaling operation will be attempted without Lifecycle Management capabilities.

Category:
Elasticity

Cause:
A suitable Lifecycle Management end point was not found while performing a scaling operation on the cluster.

Action:
No action is required.

BEA-2162708
{0}: Unable to scale cluster {1} by the requested amount of {2}, adjusting scaling request to {3} instances.

Category:
Elasticity

Cause:
The requested capacity likely exceeded the MaxDynamicClusterSize setting for the cluster.

Action:
If necessary, increase the MaxDynamicClusterSize on the DynamicServersMBean for the cluster. This may, however, also require that you provision additional hardware capacity.

BEA-2162709
{0}: Scaling operation failed to start server {2} for cluster {1}.

Category:
Elasticity

Cause:
Server startup failed. Check the server log to determine why the startup failed.

Action:
Determine what caused the startup to fail, and take corrective action.

BEA-2162710
{0}: Cluster {1} scale up, server {2} successfully started.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action is required.

BEA-2162711
{0}: Scale up work for cluster {1} completed, started {2} new instances.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162712
{0}: The workflow operation status for the scale-up work was null.

Category:
Elasticity

Cause:
The scale-up work may not be configured correctly, or this could be a product defect.

Action:
Check the server log and contact My Oracle Support if necessary.

BEA-2162713
Current size of dynamic cluster {0} is already at maximum: {1}

Category:
Elasticity

Cause:
The dynamic cluster size maximum was reached.

Action:
No action is required.

BEA-2162714
Updating max servers count for {0} by {1} to {2}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action is required.

BEA-2162715
Failed to perform forced shutdown on server {0} during scaledown operation on cluster {1}. {2}

Category:
Elasticity

Cause:
There may be an environmental problem.

Action:
Check other log messages in the log for details.

BEA-2162716
Unable to locate ServerLifecycleRuntimeMBean instance for {0}.

Category:
Elasticity

Cause:
This can result when the cluster size was not successfully adjusted to meet the requested capacity, but the scale-up was attempted.

Action:
Check the scaling action and DynamicServersMBean configuration for problems. If a defect is suspected, contact My Oracle Support.

BEA-2162717
{0}: Scale down of server {1} completed successfully for cluster {2}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162718
An unexpected exception occurred trying to start server {0} in cluster {1}. {2}

Category:
Elasticity

Cause:
An unexpected exception occurred.

Action:
Check the server log for other messages for more details.

BEA-2162719
Adjusting maximum servers count by requested amount {1} for cluster {0}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162720
{0}: Scaling operation failed to stop server {2} for cluster {1}.

Category:
Elasticity

Cause:
Server shutdown failed, check the server log to determine why the startup failed.

Action:
Determine what caused the shutdown to fail, and take corrective action.

BEA-2162721
{0}: Scale down work for cluster {1} completed, stopped {2} instances.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162722
{0}: The workflow operation status for the scale-down work was null.

Category:
Elasticity

Cause:
The scale down work may be misconfigured, or this could be a product defect.

Action:
Check the server log and contact My Oracle Support if necessary.

BEA-2162723
{0}: Graceful shutdown of server {1} in cluster {2} failed. Performing a forceful shutdown on the server.

Category:
Elasticity

Cause:
Graceful shutdown may not finish due to reasons such as sessions that may not have migrated within the specified timeout period.

Action:
If more time will be needed for quiescing the server before shutdown, increase the value of the DynamicClusterShutdownTimeoutSeconds attribute in the DynamicServersMBean for the cluster.

BEA-2162724
{0}: ScriptExecutorCommand executing pre-processor script {1} as configured in script MBean {2} while performing scale up operation for cluster {3}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162725
{0}: ScriptExecutorCommand executing pre-processor script {1} as configured in script MBean {2} while performing scale down operation for cluster {3}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162726
{0}: ScriptExecutorCommand executing post-processor script {1} as configured in script MBean {2} while performing scale up operation for cluster {3}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162727
{0}: ScriptExecutorCommand executing post-processor script {1} as configured in script MBean {2} while performing scale down operation for cluster {3}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162728
{0}: Pre-processor script {1} as configured in script MBean {2} completed with exit code {4} while performing scale up operation for cluster {3}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162729
{0}: Pre-processor script {1} as configured in script MBean {2} completed with exit code {4} while performing scale down operation for cluster {3}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162730
{0}: Post-processor script {1} as configured in script MBean {2} completed with exit code {4} while performing scale up operation for cluster {3}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162731
{0}: Post-processor script {1} as configured in script MBean {2} completed with exit code {4} while performing scale-down operation for cluster {3}.

Category:
Elasticity

Cause:
This is an informational message..

Action:
No action required.

BEA-2162732
ScriptInterceptor adding workflow item for pre-processor script {0} as configured in script MBean {1} for performing scale-up operation for cluster {2}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162733
ScriptInterceptor adding workflow item for pre-processor script {0} as configured in script MBean {1} for performing scale-down operation for cluster {2}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162734
ScriptInterceptor adding workflow item for post-processor script {0} as configured in script MBean {1} for performing scale-up operation for cluster {2}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162735
ScriptInterceptor adding workflow item for post-processor script {0} as configured in script MBean {1} for performing scale-down operation for cluster {2}.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action required.

BEA-2162736
{0}: Script interceptor {2} timed out after {4} seconds while executing script {1} for cluster {3}.

Category:
Elasticity

Cause:
The script did not complete within the specified timeout. The script may be hung or executing slower than expected.

Action:
Investigate if the script is hung or depending on resources that may not be responding. Adjust the timeout settings if necessary.

BEA-2162737
{0}: Script interceptor {2} failed with exit status {4} while executing script {1} for cluster {3}.

Category:
Elasticity

Cause:
One or more commands executed by the script failed. In addition, the script may have errors or the interceptor may not be configured correctly.

Action:
Check the configuration of the script interceptor and check for errors in the script or its configuration.

BEA-2162738
{0}: An unexpected exception occurred while trying to cancel the scale-up operation for server {2} in cluster {1}: {3}

Category:
Elasticity

Cause:
An unexpected exception occurred.

Action:
Check the server log.

BEA-2162739
{0}: An unexpected exception occurred while trying to cancel the scale-down operation for server {2} in cluster {1}: {3}

Category:
Elasticity

Cause:
An unexpected exception occurred.

Action:
Check the server log.

BEA-2162740
{0}: Server {1} cannot participate in scaling operation because its NodeManager is either not configured correctly or not reachable.

Category:
Elasticity

Cause:
NodeManager for the server is either not configured correctly or is unreachable.

Action:
Check the Machine and NodeManager configuration for the server and ensure that the NodeManager is running properly.

BEA-2162741
{0}: Aborting execution of script {1} due to cancel or timeout.

Category:
Elasticity

Cause:
The script executed by a ScriptInterceptor was aborted due to a cancel operation or timeout.

Action:
No action required.

BEA-2162742
Scaling operation with Lifecycle Management endpoint {0} failed. Please check endpoint configuration and ensure that the lifecycle runtime service is running.

Category:
Elasticity

Cause:
The lifecycle management endpoint may be misconfigured, or the lifecycle runtime service may not be running or is accessible.

Action:
Ensure that the url and credential information of the lifecycle management endpoint is correct. Ensure also that the lifecycle runtime service is running and accessible from the Administration Server.

BEA-2162743
An unexpected exception occurred trying to shut down server {0} in cluster {1}. {2}

Category:
Elasticity

Cause:
An unexpected exception occurred.

Action:
Check the server log for other messages for more details.

BEA-2162744
An error occurred while trying to update size for cluster {0}. {2}

Category:
Elasticity

Cause:
The configuration update failed. It may be due to several factors such as locked down configuration, timeouts, or another issue.

Action:
Check the server log for other messages for more details.

BEA-2162745
{0}: An error occurred trying to scale cluster {1}. Scaling operation failed because there is another scaling activity occurring on cluster {1} .

Category:
Elasticity

Cause:
The scaling operation failed because there is another scaling activity occurring on the same cluster.

Action:
Initiate the scaling activity after the current activity finishes.

BEA-2162746
{0}: An error occurred while trying to scale cluster {1}. Scaling operation failed because the cluster {1} is in cool-off period and cannot be scaled for another {2} seconds.

Category:
Elasticity

Cause:
The scaling operation failed because the cluster cannot be scaled during the cool-off period.

Action:
Initiate the scaling activity after the specified cool-off period.

BEA-2162747
{0}: Scale-up operation on cluster {1} started.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action is required.

BEA-2162748
{0}: Scale-down operation on cluster {1} started.

Category:
Elasticity

Cause:
This is an informational message.

Action:
No action is required.

BEA-2163000
OSGi system {2} could not install bundle from file {0} due to {1}

Category:
OSGi

Cause:
The OSGi system failed to install a bundle from a file.

Action:
Fix the problem that is indicated in the error message and then restart the server.

BEA-2163001
OSGi system {2} could not advertise data source {0} due to {1}

Category:
OSGi

Cause:
The OSGi system failed to advertise a data source.

Action:
Fix the problem that is indicated in the error message and then restart the server.

BEA-2163002
OSGi system {0} could not install bundles from $WL_HOME/server/osgi-lib.

Category:
OSGi

Cause:
At least one bundle from the $WL_HOME/server/osgi-lib directory could not be installed.

Action:
Examine the bundles that failed to install, fix them, and then restart the server.

BEA-2163003
Started OSGi system {0}.

Category:
OSGi

Cause:
An OSGi system has started.

Action:
Write modular code and deploy it onto your OSGi system.

BEA-2163004
OSGi system {2} could not advertise work manager {0} due to {1}

Category:
OSGi

Cause:
The OSGi system failed to advertise a work manager

Action:
Fix the problem that is indicated in the error message and then restart the server.

BEA-2163005
An application could not be deployed because it had conflicting OSGi framework names in its metadata. The OSGi framework names {0} and {1} were found.

Category:
OSGi

Cause:
More than one OSGi system was referenced in the application metadata files.

Action:
Modify the metadata files of the application such that the application references only one framework.

BEA-2163006
An application could not be deployed because it had conflicting OSGi bundle symbolic names in its metadata. The bundle symbolic names {0} and {1} were found.

Category:
OSGi

Cause:
More than one OSGi bundle was referenced in the application metadata files.

Action:
Modify the metadata files of the application such that the application references only one bundle.

BEA-2164000
The specified partition "{0}" does not exist in the domain.

Category:
Deployer

Cause:
A partition needs to exist in the domain before deploying to it.

Action:
Create the specified partition before deploying to it.

BEA-2164001
Start and stop operations are not supported for resources at the resource group template level.

Category:
Deployer

Cause:
Start and stop operations are not supported for resources at the resource group template level.

Action:
Start and stop resources at the referencing resource group level.

BEA-2164002
The specified resource group "{0}" does not exist in the specified partition "{1}".

Category:
Deployer

Cause:
A resource group needs to exist before deploying to it.

Action:
Create the specified resource group before deploying to it.

BEA-2164003
The specified resource group template "{0}" does not exist in the domain.

Category:
Deployer

Cause:
A resource group template needs to exist before deploying to it.

Action:
Create the specified resource group template before deploying to it.

BEA-2164004
The resource group name cannot be derived in this case. Specify the resource group option along with the partition option.

Category:
Deployer

Cause:
A resource group option must be specified with the partition option in cases where it cannot be derived.

Action:
Specify the resource group option with the partition option.

BEA-2164005
A resource group template option cannot be specified with a resource group option.

Category:
Deployer

Cause:
A resource group template option and resource group option were specified together.

Action:
Either specify the resource group template option or specify the resource group option.

BEA-2164007
The specified resource group "{0}" does not exist in the domain.

Category:
Deployer

Cause:
A resource group needs to exist before you can deploy to it.

Action:
Create the specified resource group before deploying to it.

BEA-2164008
The override of the deployment plan was already removed.

Category:
Deployer

Cause:
The override of the plan cannot be removed because it was already removed.

Action:
No action is required.

BEA-2164009
A resource group template option cannot be specified in a partition context.

Category:
Deployer

Cause:
A partition administrator cannot operate on a resource group template.

Action:
Operate on a resource group template outside of the partition context.

BEA-2164011
A resource group option cannot be specified in this operation.

Category:
Deployer

Cause:
A resource group option was specified but is not supported in this operation.

Action:
Retry the operation without the resource group option.

BEA-2164012
Unable to perform the {1} request for application "{0}". Either the application does not exist, or it is deployed to a resource group template referenced by resource group "{2}".

Category:
Deployer

Cause:
The application name was likely misspelled, or it is deployed to a resource group template but no resourceGroupTemplate option value was provided.

Action:
Verify that the application is correctly named, or provide a resource group template name using the resourceGroupTemplate option if application is deployed to a resource group template, or remove the reference to the resource group template from the resource group.

BEA-2164013
Unable to perform the {1} request for application "{0}". Operation cannot be performed until the server is restarted. Either the application does not exist, or it is deployed to a resource group template referenced by resource group "{2}".

Category:
Deployer

Cause:
The application name was either misspelled, was created after non-dynamic changes were activated, or it is deployed to a resource group template but no resourceGroupTemplate option value is provided. The server needed to be restarted.

Action:
Verify that the application is correctly named, or provide a resource group template name using the resourceGroupTemplate option if the application is deployed to a resource group template, or remove the reference to the resource group template from the resource group. Then restart the server and start the application. In the future, start the application before making non-dynamic changes to the configuration.

BEA-2164014
The deployment task "{0}" for application "{1}" was canceled.

Category:
Deployer

Cause:
The deployment task was canceled by the adminstrator or due to an error.

Action:
No action is required if the the task was explicitly canceled.

BEA-2164015
Application or library version must be specified during undeployments from a resource group template if more than one version exists.

Category:
Deployer

Cause:
It is not possible to find our the active version given a resource group template because the state of an application is defined in the context of a partition, not by a resource group template alone.

Action:
If the intent it to undeploy the application or library from all partitions that refer to this resource group template, provide version information for this application or library.

BEA-2164016
Cannot start an application which is in a shutdown partition {0} or resource group {1}.

Category:
Deployer

Cause:
An administrator is trying to start an application which is in a shutdown partition or resource group.

Action:
An application will be started when the partition or resource group is started.

BEA-2164017
Implicitly retiring {0} during managed server startup

Category:
Deployer

Cause:
A newer version of the application could have been deployed since this server was last booted

Action:
No action needs to be taken

BEA-2164018
More than one non-retiring app ids found on server startup: {0}

Category:
Deployer

Cause:
The older version might not have been retired yet

Action:
No action needs to be taken

BEA-2164019
More than one retiring app ids found on server startup: {0}

Category:
Deployer

Cause:
A newer version of the application could have been deployed since this server was last booted

Action:
More than one production redeploy might have been performed

BEA-2164020
There is no application named "{0}" in the system. However, there is a pending configuration change which does have an application named "{0}". The user must decide to either delete the pending transaction or commit the pending transaction before the {1} operation can be performed.

Category:
Deployer

Cause:
It is either because the user has started a configuration edit transaction but has not yet committed it yet, or it is possible that an existing edit transaction was underway and the admin server has rebooted. In either case some user must decide to either abandon the existing user transaction or commit the existing user transaction to perform the operation given in the message.

Action:
Some administrative user must decide to either abandon the existing configuration transaction or to commit the existing configuration transaction before issuing this command to the given application.

BEA-2164021
Application {0} is marked for retirement at {1} in future. This app will not be implicitly retired at this time {2}

Category:
Deployer

Cause:
The reiterment time is valid but set to some time in the future

Action:
No action needs to be taken

BEA-2164022
Entry for module {1} is being removed from app runtime state of application {0} during server startup

Category:
Deployer

Cause:
Applciation source could have changed while the server was shutdown

Action:
No action needs to be taken

BEA-2164023
Failed to deploy new version {1} of configured application {0} {3}

Category:
Deployer

Cause:
Underlying exception in deployment {4}

Action:
Address the underlying exception. If the exception is because of the new version, fix it and introduce it as a new version

BEA-2164024
Failed to properly retire old version {1} of configured application {0} {2}

Category:
Deployer

Cause:
Underlying exception in deployment {3}

Action:
No action needs to be taken

BEA-2164025
Failed to read deployment-config-overrides.xml file at path {0} {1}

Category:
Deployer

Cause:
Underlying exception in deployment {2}

Action:
Address the underlying exception and fix the problem with file system

BEA-2164026
Initiating deployment of new version of configured application {0}. The new generated version is {1} and it will be deployed from {2}

Category:
Deployer

Cause:
The new version of application must have been specified in a the updated deployment-config-overrides.xml

Action:
No action needs to be taken at this time

BEA-2164027
Completed deployment of new generated version {1} of configured application {0}

Category:
Deployer

Cause:
The new version of application must have been specified in a the updated deployment-config-overrides.xml

Action:
No action needs to be taken at this time

BEA-2164028
Scheduling retirement for generated version {1} of configured application {0} in {2} seconds

Category:
Deployer

Cause:
The new version of application must have been specified in a the updated deployment-config-overrides.xml. That version must have successfully deployed, so the old version is being retired

Action:
No action needs to be taken at this time

BEA-2164029
Initiating retirement of old generated version {1} of configured application {0}

Category:
Deployer

Cause:
The new version of application must have been specified in a the updated deployment-config-overrides.xml. That version must have successfully deployed, so the old version is being retired

Action:
No action needs to be taken at this time

BEA-2164030
Completed retirement of old generated version {1} of configured application {0}

Category:
Deployer

Cause:
The new version of application must have been specified in a the updated deployment-config-overrides.xml. That version must have successfully deployed, so the old version is being retired

Action:
No action needs to be taken at this time

BEA-2164031
Ignoring a modified deployment-config-overrides.xml because previous processing started at {0} has not completed yet

Category:
Deployer

Cause:
Changes to deployment-config-overrides.xml from a previous poll are still being processed. So the current poll will be ignored

Action:
No action needs to be taken at this time

BEA-2164032
Cancelling {2} for generated version {1} of {0} since MSID infrastructure is being torn down

Category:
Deployer

Cause:
MSID infrastructure is being torn down, most likely due to server shutdown. All in-flight work will be cancelled.

Action:
No action needs to be taken at this time

BEA-2164033
Invalid value of retire-timeout {2} found in deployment-config-overrides.xml for generated version {1} of {0}. This value must be a non-negative integer. This value is being ignored, domain wide default {3} will be used instead

Category:
Deployer

Cause:
Retire timeout configuration cannot be processed if it is not a number, or if it is negative.

Action:
Correct the value of retire-timeout in deployment-config-overrides.xml

BEA-2164034
The processing of the MSID application [{0}] is blocked. Current count of old app version [{1}] reaches the maxiumum number of old app versions [{2}] threshold.

Category:
Deployer

Cause:
The current count of old app version reaches max old app versions threshold. Processing of the next MSID application is blocked till the count drops below the threshold.

Action:
You can wait for the count of old app version drops below the threshold, or configure the max-old-app-versions property in DeploymentConfigOverridesMBean to increase the threshold.

BEA-2164035
The processing of the MSID application is unblocked. Current count of old app version [{0}] drops below the maximum number of old app versions [{1}] threshold.

Category:
Deployer

Cause:
The current count of old app version drops below max old app versions threshold. Processing of the next MSID application is now unblocked.

Action:
No action needs to be taken at this time

BEA-2164036
An attempt was made to execute the "{0}" operation on an application named "{1}" that is not currently available. The application may have been created after non-dynamic configuration changes were activated; or this server has gone out-of-sync with the admin server so it is unaware of the application. Allow the "{0}" operation to pass through so it does not affect "{0}" operation performed on other in-sync server instances. Please restart this server at earliest convenience to get things back in sync.

Category:
Deployer

Cause:
The application may have been created after non-dynamic changes were activated, or this server has gone out-of-sync with the admin server so it is unaware of the application.

Action:
Restart the server at earliest convenience to get things back in sync.

BEA-2165000
Resource Consumption Management service initialization started.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165001
Resource Consumption Management service initialization completed.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165002
Resource Consumption Management resource class was not found. An error occurred during initialization: {0}

Category:
RCM

Cause:
A resource class name was not found.

Action:
Check the "config.xml" file. Verify the resource class name or the configuration.

BEA-2165003
Resource Consumption Management resource runtime MBean is not registered. An error occurred during initialization of runtime MBeans: {0}

Category:
RCM

Cause:
There was an error while registering runtime MBeans.

Action:
Check the exception for the exact error message.

BEA-2165004
Trigger value is updated for an Resource Consumption Management resource.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165005
New trigger is added to an Resource Consumption Management resource.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165006
Trigger is removed for an Resource Consumption Management resource.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165007
Resource Consumption Management resource is added to Resource Manager.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165008
Resource Consumption Management Resource is removed from Resource Manager.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165009
Resource Consumption Management resource manager is added to Resource Management.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165010
Resource Consumption Management resource manager is removed from Resource Management.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165011
Resource Consumption Management resource manager is added to the partition.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165012
Resource Consumption Management resource manager is removed from the partition.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165013
Updating resource manager reference at the partition.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165014
Updating resource manager reference at the partition, moving current usage to the new resource manager.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165015
Trying to update a resource manager reference at the partition but can not proceed as Current Usage is more than the new value specified at the Trigger level.

Category:
RCM

Cause:
Current Usage was more than the new value specified at the Trigger level.

Action:
Increase the Trigger value for a shutdown or fail action.

BEA-2165016
FairShare is removed for the Resource Consumption Management resource.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165017
New FairShare is added to the Resource Consumption Management resource.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165018
Resource Consumption Management Notification Withdraw Message: Notification action has been withdrawn because the quota has been reached below the given trigger value.

Category:
RCM

Cause:
This is an informational message for a withdrawal notification action under Resource Consumption Management.

Action:
This is a log message based on a "notify" trigger specified for the resource under Resource Consumption Management. If you want, you can use the WebLogic Diagnostic Framework(WLDF) to define different rules for this notification.

BEA-2165019
"ResourceManagement" is not supported in this JDK. Use Oracle JDK 8u40 or later which supports "ResourceManagement", to use the WebLogic Server "Resource Consumption Management" feature.

Category:
RCM

Cause:
"ResourceManagement" is not supported in the JDK used to start the WebLogic Server.

Action:
Use Oracle JDK 8u40 or later.

BEA-2165020
FairShare was updated to the Resource Consumption Management resource.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165021
"ResourceManagement" is not enabled in this JVM. Enable "ResourceManagement" to use the WebLogic Server "Resource Consumption Management" feature. To enable "ResourceManagement", you must specify the following JVM options in the WebLogic Server instance in which the JVM runs: -XX:+UnlockCommercialFeatures -XX:+ResourceManagement.

Category:
RCM

Cause:
"ResourceManagement" is not enabled in this JVM.

Action:
Enable "ResourceManagement" to use the WebLogic Server "Resource Consumption Management" feature.

BEA-2165022
The process of creating the Resource Consumption Management Diagnostic Image has been timed out by the Diagnostic Framework. The resulting image may be incomplete.

Category:
RCM

Cause:
The process of creating the Resource Consumption Management Diagnostic Image has been timed out by the Diagnostic Framework.

Action:
Investigate the contents of the log and Diagnostic Images for more information.

BEA-2165023
Resource Consumption Management Fail Withdraw Message: Fail action has been withdrawn because the quota dropped below the given trigger value.

Category:
RCM

Cause:
This is an informational message for a withdrawal fail action under Resource Consumption Management.

Action:
This is a log message based on a fail trigger specified for the resource under Resource Consumption Management. If you want, you can use WebLogic Diagnostic Framework(WLDF) to define different rules for this notification.

BEA-2165024
"ResourceManagement" is not supported in this JDK, but found a "Resource Consumption Management" policy configuration in the WebLogic Server for partition "{0}". Use Oracle JDK 8u40 or later which supports "ResourceManagement", to use the WebLogic Server "Resource Consumption Management" feature.

Category:
RCM

Cause:
"ResourceManagement" is not supported in the JDK used to start the WebLogic Server.

Action:
Use Oracle JDK 8u40 or later.

BEA-2165025
"ResourceManagement" is not enabled in this JVM, but found a "Resource Consumption Management" policy configuration in the WebLogic Server for partition "{0}". Enable "ResourceManagement" to use the WebLogic Server "Resource Consumption Management" feature. To enable "ResourceManagement", you must specify the following JVM options in the WebLogic Server instance in which the JVM runs: -XX:+UnlockCommercialFeatures -XX:+ResourceManagement.

Category:
RCM

Cause:
"ResourceManagement" is not enabled in this JVM.

Action:
Enable "ResourceManagement" to use the WebLogic Server "Resource Consumption Management" feature.

BEA-2165026
System Accounting flag is turned on. All resources consumed for performing System work by a Partition are tracked separately and not included in the Partition"s resource consumption values. If there are any Resource Consumption Management Policies(Triggers) configured, they will not be accounting system context based resource consumption. Similarly, Partition Resource Metrics will not include system context based resource consumption.

Category:
RCM

Cause:
This is an informational message.

Action:
When "System Accounting" feature is enabled, Resource Consumption Management policies established for a Partition would not include the resources consumed for a Partition to execute System work. If the Resource Consumption Management policies established for a Partition must track all resources used for a Partition, disable the "System Accounting" feature.

BEA-2165027
"Resource Consumption Management" policy for "Heap Retained" resource is defined in the WebLogic Server for partition "{0}". However "Heap Retained Metric" is not available in WebLogic Server.Resource Consumption Management" policy for "Heap Retained" resource can not be activated if "Heap Retained Metric" is not available. "Heap Retained Metric" is

unavailable if "G1 Garbage Collector" is not enabled in the WebLogic Server JVM. Please enable "G1 Garbage Collector" to use "Heap Retained Metric" in WebLogic Server. To enable "G1 Garbage Collector", you must specify the following JVM options in the WebLogic Server instance in which the JVM runs: -XX:+UseG1GC.

Category:
RCM

Cause:
"Heap Retained Metric" is not available in WebLogic Server but found a "Resource Consumption Management" policy configuration for "Heap Retained" resource in the WebLogic Server for partition "{0}"

Action:
Enable "G1 Garbage Collector", Please specify the following JVM options in the WebLogic Server instance in which the JVM runs: -XX:+UseG1GC.

BEA-2165028
"Heap Retained Metric" is not available in WebLogic Server."Resource Consumption Management" support for "Heap Retained" resource is not available. "Heap Retained" resource is available only with "G1 Garbage Collector".

Category:
RCM

Cause:
"Heap Retained Metric" is not available in WebLogic Server.

Action:
If "Resource Consumption Management" support for "Heap Retained" resource is needed , please enable "G1 Garbage Collector" by specifying the following JVM options in the WebLogic Server instance in which the JVM runs:-XX:+UseG1GC.

BEA-2165029
Resource Consumption Management Restart Message: Given quota has been reached for the partition and a "restart" action has been executed.

Category:
RCM

Cause:
Given quota for the resource under Resource Consumption Management was reached for the partition and a "restart" action was executed. The partition was restarted due to this action.

Action:
No action is required.

BEA-2165030
Resource Consumption Management Restart Message: Partition has been restarted the maximum number of times as a result of resource consumption management "restart" action, in the duration, as specified in the partition config. Partition can not be restarted anymore, and is being shutdown.Partition would have to be started manually.

Category:
RCM

Cause:
There are many attempts to "restart" the partition in configured duration.In order to prevent restart action going in a loop ,a "shutdown" action is executed.

Action:
There are many attempts to "restart" the partition in configured duration. You can reconfigure max-restart-allowed and max-restart-allowed-interval with higher value if this is expected behaviour .

BEA-2165031
Resource Consumption Management : Partition restart is unsuccessful. It failed with an error : {0}

Category:
RCM

Cause:
There was an error while restarting the partition.

Action:
Check the exception for the exact error message.

BEA-2165032
Restart Loop Protection updated for a Resource Consumption Management Resource Manager.

Category:
RCM

Cause:
This is an informational message.

Action:
No action is required.

BEA-2165799
Resource Consumption Management Notification Message: Given quota has been reached for the partition and a "notify" action has been executed.

Category:
RCM

Cause:
Given quota for the resource under Resource Consumption Management was reached for the partition and a "notify" action was executed.

Action:
This is a log message based on a "notify" trigger specified for the resource under Resource Consumption Management. If you want, you can use the WebLogic Diagnostic Framework(WLDF) to define different rules for this notification.

BEA-2165800
Resource Consumption Management Slow Message: Given quota has been reached for the partition and a "slow" action has been executed.

Category:
RCM

Cause:
Given quota for the resource under Resource Consumption Management was reached for the partition and a "slow" action was executed.The partition was slowed down due to this action.Once the resource consumption drops below the specified quota, partition would be un-slowed.

Action:
No action is required.

BEA-2165801
Resource Consumption Management Shutdown Message: Given quota has been reached for the partition and a "shutdown" action has been executed.

Category:
RCM

Cause:
Given quota for the resource under Resource Consumption Management was reached for the partition and a "shutdown" action was executed. The partition was stopped due to this action.

Action:
The partition has been stopped. Restart the partition manually. Use the Administration Console or WebLogic Diagnostic Framework(WLST) to start the partition.

BEA-2165802
Resource Consumption Management Fail Message: Given quota has been reached for the partition and a "fail" action has been executed.

Category:
RCM

Cause:
Given quota for the resource under Resource Consumption Management was reached for the partition and a "fail" action was executed. The resource consumption request failed due to this action.

Action:
Reissue the request.

BEA-2165803
Resource Consumption Management Un-slow Message: Slow action is "withdraw" as quota has been reached below the given trigger value.

Category:
RCM

Cause:
Slow action was withdrew as quota reached below the given trigger value for the resource under Resource Consumption Management .

Action:
No action is required.

BEA-2165804
Resource Consumption Management : Unable to successfully execute action {0}. It failed with an error : {1}

Category:
RCM

Cause:
There was an error while executing the indicated action.

Action:
Check the exception for the exact error message.

BEA-2165805
Resource Consumption Management : Unable to successfully withdraw action {0}. It failed with an error : {1}

Category:
RCM

Cause:
There was an error while withdrawing the indicated action.

Action:
Check the exception for the exact error message.

BEA-2166001
Message "{0}" Exception: {1}

Category:
LCM

Cause:
This message displays output from the script.

Action:
No action is required.

BEA-2166002
Exception Loading Plugins during LCM bootstrap: {0}

Category:
LCM

Cause:
Details of the cause are provided in the exception.

Action:
Ensure LCM Plugins are in Plugin directory.

BEA-2166003
Exception getting the LCM Configuration File: {0}

Category:
LCM

Cause:
Details of the cause are provided in the exception.

Action:
Ensure LCM Configuration file is present in Domain Config Directory.

BEA-2166004
Exception Setting up File Watcher for LCM Configuration File: {0}

Category:
LCM

Cause:
Details of the cause are provided in the exception.

Action:
Ensure LCM Configuration file is present in Domain Config Directory.

BEA-2166005
Exception reloading LCM Configuration File: {0}

Category:
LCM

Cause:
Details of the cause are provided in the exception.

Action:
Ensure LCM Configuration file is present in Domain Config Directory.

BEA-2166201
Could not shutdown server {0}

Category:
LCM_WLS_Plugin

Cause:
Details of the cause are provided in the exception.

Action:
Take appropriate action based on the details provided in the exception.

BEA-2166202
Could not shutdown server {0}

Category:
LCM_WLS_Plugin

Cause:
Details of the cause are provided in the exception.

Action:
Take appropriate action based on the details provided in the exception.

BEA-2166203
Could not get server mbean details for {0}

Category:
LCM_WLS_Plugin

Cause:
Details of the cause are provided in the exception.

Action:
Take appropriate action based on the details provided in the exception.

BEA-2190000
{0} ERROR DATA recv on CLOSED messageId {1} frameType: {2} flags: {3} subprotocol: {4} messageId: {5}

Category:
BuzzMessageBus

Cause:
Data was received after the message was closed.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190001
{0} ERROR DATA recv on zero messageId {1} frameType: {2} flags: {3} subprotocol: {4} messageId: {5}

Category:
BuzzMessageBus

Cause:
Data was received with an illegal messageId.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190002
{0} ERROR INIT recv after INIT, releasing endpoint {1} peer: {2}/{3} local: {4}/{5}

Category:
BuzzMessageBus

Cause:
An INIT was received after a previous INIT.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190003
{0} ERROR INIT recv frame too short {1}

Category:
BuzzMessageBus

Cause:
An INIT frame was received that is not long enough.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190004
{0} ERROR INIT recv version mismatch {1} peer: {2}/{3} local: {4}/{5}

Category:
BuzzMessageBus

Cause:
An INIT frame was received with version information that cannot be matched.

Action:
Verify that the correct versions of all software are installed. If the problem persists, contact My Oracle Support and provide them with the logs.

BEA-2190005
{0} ERROR message received before connection initialized {1} frameType: {2} flags: {3} subprotocol: {4} messageId: {5}

Category:
BuzzMessageBus

Cause:
A message was received before the connection was initialized.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190006
{0} ERROR recv message too short {1} bytes: {2}

Category:
BuzzMessageBus

Cause:
A received message was too short.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190007
{0} START recv for existing messageId {1} flags: {2} subprotocol: {3} messageId: {4}

Category:
BuzzMessageBus

Cause:
A START frame was received for an existing messageId.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190008
{0} ERROR ignoring START message received on endpoint in GRACEFUL_SHUTDOWN state {1} flags: {2} subprotocol: {3} messageId: {4} connectionState: {5}

Category:
BuzzMessageBus

Cause:
A START frame was received but the endpoint is shutting down.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190009
{0} ERROR START recv on messageId zero {1} flags: {2} subprotocol: {3}

Category:
BuzzMessageBus

Cause:
A START was received with an illegal messageId.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190010
{0} ERROR recv subprotocol mismatch {1} frameType: {2} flags: {3} subprotocol: {4} messageId: {5} subprotocol of previous message {6}

Category:
BuzzMessageBus

Cause:
A message was received with a subprotocol that does not match the previous subprotocol for the same messageId.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190011
{0} ERROR recv unknown error code {1} frameType: {2} flags: {3} subprotocol: {4} messageId: {5} errorCode: {6}

Category:
BuzzMessageBus

Cause:
A message was received with an unknown error code.

Action:
Verify that the correct versions of all software are installed. If the problem persists, contact My Oracle Support and provide them with the logs.

BEA-2190012
{0} ERROR recv unknown frame type {1} frameType: {2} flags: {3} subprotocol: {4} messageId: {5}

Category:
BuzzMessageBus

Cause:
A message was received with an unknown frame type.

Action:
Verify that the correct versions of all software are installed. If the problem persists, contact My Oracle Support and provide them with the logs.

BEA-2190013
{0} ERROR INTERNAL open or close admin receiver threw exception (ignored) {1} adminReceiver: {2}

Category:
BuzzMessageBus

Cause:
A BuzzAdminReceiver threw an exception in its #close or #open method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190014
{0} ERROR INTERNAL graceful shutdown ack received admin receiver threw exception (ignored) {1} adminReceiver: {2}

Category:
BuzzMessageBus

Cause:
A BuzzAdminReceiver threw an exception in its #gracefulShutdown method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190015
{0} ERROR INTERNAL graceful shutdown ack admin receiver threw exception (ignored) {1} adminReceiver: {2}

Category:
BuzzMessageBus

Cause:
A BuzzAdminReceiver threw an exception in its #gracefulShutdown method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190016
{0} ERROR INTERNAL connect or release receiver threw exception (ignored) {1} subprotocol: {2} subprotocolReceiver: {3} eventType: {4}

Category:
BuzzMessageBus

Cause:
A BuzzSubprotocolReceiver threw an exception in its #connect or #release method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190017
{0} ERROR INTERNAL receipt receiver threw exception (ignored) {1} subprotocol: {2} subprotocolReceiver: {3} receiptCookie: {4}

Category:
BuzzMessageBus

Cause:
A BuzzSubprotocolReceiver threw an exception in its #receipt method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190018
{0} ERROR INTERNAL backlog receiver threw exception (ignored) {1} subprotocol: {2} subprotocolReceiver: {3} isExcessive: {4}

Category:
BuzzMessageBus

Cause:
A BuzzSubprotocolReceiver threw an exception in its #backlog method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190019
{0} ERROR INTERNAL graceful shutdown ack sent done receiver threw exception (ignored) {1} subprotocol: {2} subprotocolReceiver: {3}

Category:
BuzzMessageBus

Cause:
A BuzzSubprotocolReceiver threw an exception in its #gracefulShutdown method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190020
{0} ERROR INTERNAL subprotocol receiver threw exception (ignored) {1} frameType: {2} flags: {3} subprotocol: {4} messageId {5} subprotocolReceiver: {6}

Category:
BuzzMessageBus

Cause:
A BuzzSubprotocolReceiver threw an exception in its #receive method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190021
{0} ERROR INTERNAL graceful shutdown receiver threw exception (ignored) subprotocol: {1} subprotocolReceiver: {2} gracefulShutdownState: {3}

Category:
BuzzMessageBus

Cause:
A BuzzSubprotocolReceiver threw an exception in its #gracefulShutdown method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190022
{0} ERROR INTERNAL subprotocol internal receiver threw exception (ignored) {1} frameType: {2} flags: {3} subprotocol: {4} messageId: {5} subprotocolReceiver: {6}

Category:
BuzzMessageBus

Cause:
A BuzzSubprotocolReceiverInternalApi threw an exception in its #receiveRstInternal method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190023
{0} ERROR INTERNAL graceful shutdown internal receiver threw exception (ignored) {1} subprotocol: {2} errorCode: {3} subprotocolReceiver: {4}

Category:
BuzzMessageBus

Cause:
A BuzzSubprotocolReceiverInternalApi threw an exception in its #receiveGsdInternal method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190024
{0} ERROR INTERNAL EventCollector exception (ignored) {1}

Category:
BuzzMessageBus

Cause:
Collector.add threw an exception which will be ignored.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190025
{0} ERROR exception in tryRelase (ignored) {1} extra: msg

Category:
BuzzMessageBus

Cause:
An exception occurred in TryRelease (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190026
{0} ERROR INTERNAL POTENTIAL RDMA MEMORY LEAK no subprotocol receiver for receipt cookie {1} receiptCookie: {2}

Category:
BuzzMessageBus

Cause:
There is no subprotocol receiver for the receipt cookie. This may be due to an RDMA memory leak.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190027
{0} ERROR INTERNAL incorrect event type in connect release receiver {1} eventType: {2}

Category:
BuzzMessageBus

Cause:
There is an INTERNAL incorrect event type in the connect release receiver.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190028
{0} ERROR INTERNAL POTENTIAL RDMA MEMORY LEAK unknown receipt type {1} receiptCookie: {2}

Category:
BuzzMessageBus

Cause:
An unknown receipt type was encountered. This may be due to an RDMA memory leak.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190029
{0} ERROR INTERNAL recv exception reading BufferSequenceInputStream {1} bytes: {2}

Category:
BuzzMessageBus

Cause:
An exception occurred while reading BufferSequenceInputStream.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190030
{0} ERROR INTERNAL POTENTIAL RDMA MEMORY LEAK forceCloseIdAux message info is null {1} messageId {2}

Category:
BuzzMessageBus

Cause:
INTERNAL MessageInfo is null. This may be due to an RDMA memory leak.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190031
{0} ERROR INTERNAL no ConnectionInfo {1}

Category:
BuzzMessageBus

Cause:
No connection info was provided for the endpoint.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190032
{0} ERROR INTERNAL no epToMessageMap entry {1}

Category:
BuzzMessageBus

Cause:
The epToMessageMap entry for the endPoint was missing.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190033
{0} ERROR INTERNAL recv no subprotocol receiver {1} frameType: {2} flags: {3} subprotocol: {4} messageId: {5}

Category:
BuzzMessageBus

Cause:
No subprotocol receiver was provided for the messageId.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190034
{0} ERROR INIT INTERNAL recv connection in wrong state, should be CONNECTED {1} peer: {2}/{3} local: {4}/{5} connectionState: {6}

Category:
BuzzMessageBus

Cause:
An INIT frame was received but the endpoint is in the wrong state.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190035
{0} ERROR INTERNAL INIT recv error ConnectionInfo should not be null {1}

Category:
BuzzMessageBus

Cause:
An INTERNAL INIT was received but ConnectionInfo is null.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190036
{0} ERROR INTERNAL POTENTIAL RDMA MEMORY LEAK recv unknown messageId scope for RST {1} flags: {2} subprotocol: {3} messageId: {4} errorCode: {5}

Category:
BuzzMessageBus

Cause:
An RST frame was received with an unknown messageId scope. This may be due to an RDMA memory leak.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190037
{0} ERROR INTERNAL send incorrect message state - should be HALF_CLOSED {1} frameType: {2} flags: {3} subprotocol: {4} messageId: {5} messageState: {6}

Category:
BuzzMessageBus

Cause:
An attempt was made to send a message but the message is in an incorrect state.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190038
{0} ERROR INTERNAL send incorrect message state - should be OPEN {1} frameType: {2} flags: {3} subprotocol: {4} messageId: {5} messageState: {6}

Category:
BuzzMessageBus

Cause:
An INTERNAL attempt was made to send a message but the message is in an incorrect state.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190039
{0} ERROR INTERNAL send existing endPoint to ConnectionInfo during INIT {1}

Category:
BuzzMessageBus

Cause:
An error of type INTERNAL occurred during initialization.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190040
{0} ERROR INTERNAL send exception when sending RST {1} subprotocol: {2} messageId: {3} errorCode: {4} extra: {5}

Category:
BuzzMessageBus

Cause:
An exception of type INTERNAL occurred when sending RST.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190041
{0} ERROR INTERNAL flush receiver threw exception (ignored) subprotocol: {1} subprotocolReceiver: {2}: {3}

Category:
BuzzMessageBus

Cause:
A BuzzSubprotocolReceiver threw an exception in its #flush method (ignored).

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190042
{0} ERROR close time out extra: waited for {1} {2}

Category:
BuzzMessageBus

Cause:
An internal close timeout occurred.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190043
Unexpected DummyBuzzChannel usage by App Container with stack trace: {0}.

Category:
BuzzMessageBus

Cause:
There was an unexpected usage of DummyBuzzChannel by the Application Container.

Action:
Contact My Oracle Support and provide them with the logs.

BEA-2190044
Buzz Message Bus is initialized at {0}.

Category:
BuzzMessageBus

Cause:
This is an informational message.

Action:
No action required.

BEA-2191000
{0} Invalid HTTP header length in Buzz frame: {1}

Category:
BuzzMessageBusHttp

Cause:
The HTTP header length in the Buzz frame is invalid.

Action:
Contact My Oracle Support and provide them the logs.

BEA-2191001
{0} Incomplete HTTP header in Buzz frame

Category:
BuzzMessageBusHttp

Cause:
The HTTP header in the Buzz frame is incomplete.

Action:
Contact My Oracle Support and provide them the logs.

BEA-2191002
{0} Invalid message type for HTTP BuzzSubprotocolHandler: {1}

Category:
BuzzMessageBusHttp

Cause:
The message type received by the HTTP BuzzSubprotocolHandler is invalid.

Action:
Contact My Oracle Support and provide them the logs.

BEA-2191003
{0} The BuzzSubprotocolRecieverHttpWLSImpl#receipt method should not be invoked. There may be a memory leak: {1}

Category:
BuzzMessageBusHttp

Cause:
The Http BuzzSubprotocolHandler encountered an internal receipt error.

Action:
Contact My Oracle Support and provide them the logs.

BEA-2191004
{0} Internal receive error in Http BuzzSubprotocolHandler: {1}

Category:
BuzzMessageBusHttp

Cause:
The Http BuzzSubprotocolHandler encountered an internal receive error.

Action:
Contact My Oracle Support and provide them the logs.

BEA-2191005
{0} A complete message could not be read on socket: '{1}', in the configured timeout period of '{2}' secs.

Category:
BuzzMessageBusHttp

Cause:
A complete HTTP message could not be read on the socket within the configured timeout.

Action:
Contact My Oracle Support and provide them the logs.

BEA-2191006
{0} BuzzSubprotocolRecieverHttpWLSImpl#closeYourId({1}) should not be invoked because WLS/Buzz/HTTP does not initiate messages.

Category:
BuzzMessageBusHttp

Cause:
BuzzSubprotocolRecieverHttpWLSImpl#closeYourId was invoked.

Action:
Contact My Oracle Support and provide them the logs.

BEA-2192000
Workflow {0} failed in step <{1}> during {2} operation without a specified reason. Requested resolution is {3}

Category:
MgmtOrchestration

Cause:
{0}

Action:
Workflow failures are handled according to their failure plan. Check the log messages or the workflow results for additional details.

BEA-2192001
Workflow {0} failed in step <{1}> during {2} operation. Requested resolution is {3}. Reason: {4}

Category:
MgmtOrchestration

Cause:
{0} - {2}

Action:
Workflow failures are handled according to their failure plan. Check the log messages or the workflow results for additional details.

BEA-2192002
Workflow {0} - the saved workflow is corrupted, there are missing work units.

Category:
MgmtOrchestration

Cause:
The workflow could not be loaded properly from persistent storage.

Action:
Review the server configuration or create a new workflow.

BEA-2192003
Workflow {0} - the saved workflow is corrupted, checksum errors were detected.

Category:
MgmtOrchestration

Cause:
The workflow could not be loaded properly from persistent storage.

Action:
Review the server configuration or create a new workflow.

BEA-2192004
Workflow {0} Running: {1} / {2}

Category:
MgmtOrchestration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192005
Workflow {0} finished successfully. {1} steps completed.

Category:
MgmtOrchestration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192006
Workflow {0} failed and the revert process has been initiated.

Category:
MgmtOrchestration

Cause:
See getError for details of the failure.

Action:
Allow the workflow to revert automatically, then diagnose the failure with the information reported by getError before attempting the process again.

BEA-2192007
Workflow {0} failed and the revert process was not initiated. The failure was: {1}

Category:
MgmtOrchestration

Cause:
See getError for details of the failure.

Action:
Diagnose the failure with the information reported by getError and address it.

BEA-2192008
Workflow {0} failed, the revert process was initiated and completed successfully. The failure that triggered the revert process was: {1}

Category:
MgmtOrchestration

Cause:
See getError for details of the failure.

Action:
Diagnose the failure with the informatipn reported by getError and address it. Then try running the procedure again.

BEA-2192009
Workflow {0} failed, the revert process was initiated, but it failed as well. The failure that triggered the revert process was: {1}

Category:
MgmtOrchestration

Cause:
See getError for details of the cause.

Action:
Review the cause details from getError and address the reported issue. The partial completion of this operation may have left affected targets in an inconsistent state.

BEA-2192010
Workflow {0} was canceled.

Category:
MgmtOrchestration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192011
Workflow {0} cannot create directory to store workflow: {0}

Category:
MgmtOrchestration

Cause:
The requested directory could not be created.

Action:
Ensure that the parent directory is writable and the hard drive has sufficient free space.

BEA-2192012
Workflow {0} could not delete a file during the workflow storage cleaning process. {1}

Category:
MgmtOrchestration

Cause:
{1}

Action:
Unlock the file and check the user's privileges.

BEA-2192013
Workflow {0} - found unexpected or invalid structures in the storage directory:{1}

Category:
MgmtOrchestration

Cause:
This is usually caused by external changes to the directory contents.

Action:
Create a new workflow for this procedure.

BEA-2192014
Workflow {0} could not move the temporary workflow file ({0}) to the permanent destination ({1}).

Category:
MgmtOrchestration

Cause:
The cause is unknown.

Action:
Ensure that the parent directory is writable and that the temporary workflow file is writable. You will likely need to start a new workflow for this procedure.

BEA-2192015
Workflow {0} is starting the revert process.

Category:
MgmtOrchestration

Cause:
There was a previously reported error with the workflow and the revert process is starting.

Action:
No action is required.

BEA-2192016
Workflow {0} is already completed and cannot be started again.

Category:
MgmtOrchestration

Cause:
You attempted to start a completed workflow.

Action:
To run the process again, start a new workflow.

BEA-2192017
Workflow {0} is already running.

Category:
MgmtOrchestration

Cause:
You attempted to start a running workflow.

Action:
No action is required.

BEA-2192018
Could not delete a file or directory: {0}

Category:
MgmtOrchestration

Cause:
Either the file is locked or the user has insufficient privileges.

Action:
Unlock the file and check the user's privileges.

BEA-2192019
Workflow {0} is not running, so it cannot be canceled.

Category:
MgmtOrchestration

Cause:
Only a running workflow can be canceled.

Action:
No action is required.

BEA-2192034
{0} {1} {2}-{3} (duration: {4})

Category:
MgmtOrchestration

Cause:
See the message body.

Action:
No action required.

BEA-2192035
{0} {1} {2}-{3} (duration: {4}) - ERROR {5}

Category:
MgmtOrchestration

Cause:
See the message body.

Action:
No action required.

BEA-2192036
{0} {1} {2}-{3} (duration: {4}) - ERROR Unknown error

Category:
MgmtOrchestration

Cause:
See the message body.

Action:
No action required.

BEA-2192037
Failure performing {1} of {0}

Category:
MgmtOrchestration

Cause:
See the cause of the exception.

Action:
Workflow failures are handled according to their failure plan. Check the log messages or the workflow results for additional details.

BEA-2192038
Workflow {0} was never executed. Cannot revert.

Category:
MgmtOrchestration

Cause:
You attempted to revert a new workflow.

Action:
This operation is valid only for stopped workflows, not for completed but already executed workflows, for example, failed workflows.

BEA-2192039
Service is blocked. It was used too early or was not used on the Administration Server.

Category:
MgmtOrchestration

Cause:
The server is not in a state where the orchestration framework can act.

Action:
Check the status of the Administration Server.

BEA-2192040
Workflow instance {0} is running. Cannot delete.

Category:
MgmtOrchestration

Cause:
A running workflow instance cannot be deleted.

Action:
Wait for the workflow to complete.

BEA-2192041
It is not possible to execute the workflow instance in its current state.

Category:
MgmtOrchestration

Cause:
The current state of the workflow is not compatible with this operation.

Action:
Check the state of the workflow instance.

BEA-2192042
It is not possible to revert the workflow instance in its current state.

Category:
MgmtOrchestration

Cause:
The current state of the workflow is not compatible with this operation.

Action:
Check the state of the workflow instance.

BEA-2192043
Cannot execute the workflow instance. Not all required shared state objects are defined. ({0})

Category:
MgmtOrchestration

Cause:
The workflow instance cannot be constructed because of missing shared state objects.

Action:
Ensure that you have defined all necessary attributes.

BEA-2192044
Failure performing {1} of {0}, caused by {2}

Category:
MgmtOrchestration

Cause:
See the cause of the exception.

Action:
Workflow failures are handled according to their failure plan. Check the log messages or the workflow results for additional details.

BEA-2192045
Debug Message: {0}

Category:
MgmtOrchestration

Cause:
Used for capturing debug information during testing.

Action:
No action is required.

BEA-2192046
Workflow {0} failed in step <{1}> during {2} operation. Requested resolution is {3}. Reason: {4}

Category:
MgmtOrchestration

Cause:
{0} - {2}

Action:
Workflow failures are handled according to their failure plan. Check the log messages or the workflow results for additional details.

BEA-2192047
Workflow {0} failed to store step <{1}> during {2} operation. Reason: {4}

Category:
MgmtOrchestration

Cause:
{0} - {2}

Action:
Workflow failures are handled according to their failure plan. Check the log messages or the workflow results for additional details.

BEA-2192048
Unable to load stored progress object of type: {0} from {1} due to {2}.

Category:
MgmtOrchestration

Cause:
{0} - {2}

Action:
Check that the file store is still valid and that the workflow information is not lost.

BEA-2192049
Unable to initialize progress object from persistence: {0} due to {1}.

Category:
MgmtOrchestration

Cause:
{0} - {1}

Action:
Check that the file store is still valid and that the workflow information is not lost.

BEA-2192050
Error initializing progress for workflow {0} from path {1}, due to {2}.

Category:
MgmtOrchestration

Cause:
{2}

Action:
Check that the file store is still valid and that the workflow information is not lost.

BEA-2192051
Error starting workflow {0}, due to {1}.

Category:
MgmtOrchestration

Cause:
{1}

Action:
Check the exception that caused the failure for more information.

BEA-2192052
Error setting type {1} on workflow {0}, {2}.

Category:
MgmtOrchestration

Cause:
{2}

Action:
Check the exception that caused the failure for more information.

BEA-2192053
Error setting target type {1} on workflow {0}, {2}.

Category:
MgmtOrchestration

Cause:
{2}

Action:
Check the exception that caused the failure for more information.

BEA-2192054
Error setting target {1} on workflow {0}, {2}.

Category:
MgmtOrchestration

Cause:
{2}

Action:
Check the exception that caused the failure for more information.

BEA-2192055
Error cleaning up workflows on Partition {0} deletion.

Category:
MgmtOrchestration

Cause:
{1}

Action:
Check the exception that caused the failure for more information.

BEA-2192056
Unable to get workflow for Partition {0} and workflowid {1}.

Category:
MgmtOrchestration

Cause:

Action:

BEA-2192057
Unable to delete workflowfiles for for Partition {0} and workflowid {1} as workflow was in state {2}.

Category:
MgmtOrchestration

Cause:

Action:

BEA-2192058
Found a workflow with state = null for Partition {0} and workflowid {1}.

Category:
MgmtOrchestration

Cause:

Action:

BEA-2192059
Error attempting to create workflow orchestration directory {0}.

Category:
MgmtOrchestration

Cause:

Action:

BEA-2192100
Script "{0}" output: {1}

Category:
Patching

Cause:
This message displays output from the script.

Action:
No action is required.

BEA-2192101
Timeout polling ready application URL for server: {0}.

Category:
Patching

Cause:
The system failed to perform a ready check on applications within the stipulated time.

Action:
Check the server log to determine which applications or applications failed to load. You may need to increase the readyCheckAppsTimeoutInMin value depending on how long the application or applications take to load.

BEA-2192102
Failed to construct URL for server: {0}.

Category:
Patching

Cause:
Details of the cause are provided in the exception.

Action:
Take appropriate action based on the details provided in the exception.

BEA-2192103
Error opening URL.

Category:
Patching

Cause:
Details of the cause are provided in the exception.

Action:
Take appropriate action based on the details provided in the exception.

BEA-2192104
Failed to get ServerLifeCycleRuntimeMBean for server {0}

Category:
Patching

Cause:
Details of the cause are provided in the exception.

Action:
Take appropriate action based on the details provided in the exception.

BEA-2192105
Server lifecycle operation error for server {0}: {1}

Category:
Patching

Cause:
Details of the cause are provided in the exception.

Action:
Take appropriate action based on the details provided in the exception.

BEA-2192106
Cannot unregister deleted MBean: {0}

Category:
Patching

Cause:
A workflow was deleted but it was not possible to unregister the relevant MBean.

Action:
No action is required.

BEA-2192107
Workflow {0} is executing {1} on {2}.

Category:
Patching

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192108
Workflow {0} is retyring {1} on {2}.

Category:
Patching

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192109
Workflow {0} is reverting {1} on {2}.

Category:
Patching

Cause:
This is an informational message.

Action:
No action isrequired.

BEA-2192110
Workflow {0} successfully completed {1} on {2}.

Category:
Patching

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192111
Workflow {0} successfully completed revert of {1} on {2}.

Category:
Patching

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192112
Workflow {0} failed to complete {1} on {2}.

Category:
Patching

Cause:
Use getError for details of the failure.

Action:
Workflow failures are handled according to their failure plan. Check the log messages or the workflow results for additional details and take appropriate action.

BEA-2192113
Workflow {0} failed to complete {1} on {2} due to error {3}.

Category:
Patching

Cause:
Use getError for details of the failure.

Action:
Workflow failures are handled according to their failure plan. Check the log messages or the workflow results for additional details and take appropriate action.

BEA-2192114
Workflow {0} failed to revert {1} on {2}.

Category:
Patching

Cause:
See the log for details of the failure.

Action:
Review the cause details from getError and address the reported issue. The partial completion of this operation may have left affected targets in an inconsistent state.

BEA-2192115
Workflow {0} failed to revert {1} on {2} due to error {3}.

Category:
Patching

Cause:
See the log for details of the failure.

Action:
Review the cause details from getError and address the reported issue. The partial completion of this operation may have left affected targets in an inconsistent state.

BEA-2192116
Unable to enable session handling features on restarted server: {0}.

Category:
Patching

Cause:
See the log for details of the failure.

Action:
Review the cause and address the reported issue. The partial completion of this operation may have left affected targets in an inconsistent state.

BEA-2192117
Targeted application redeploy for "{0}" on server "{1}" during patching failed with an exception {2}.

Category:
Patching

Cause:
See the log for details about the cause of the failure.

Action:
Review the cause in the logs and address the reported issue. The partial completion of this operation may have left affected targets in an inconsistent state.

BEA-2192118
Workflow {0} skipped {1} on {2}.

Category:
Patching

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192119
The user path input "{0}" was translated to "{1}".

Category:
Patching

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192120
Error using the NodeManager to verify local paths on machine {0}. The last lines of script output (full script output in the log): {1}.

Category:
Patching

Cause:
This is usually caused by a file not being found at the specified path.

Action:
Confirm that the specified paths are correct.

BEA-2192121
Error from ZDT agent invocation on node manager: [{0}] Message: {1}

Category:
Patching

Cause:
Operation failed while executing on node manager.

Action:
Review the cause based on the error message.

BEA-2192122
Warning from ZDT agent invocation on node manager: [{0}] Message: {1}

Category:
Patching

Cause:
Warning generated while executing on node manager.

Action:
Review the warning message.

BEA-2192123
Info from ZDT agent invocation on node manager: [{0}] Message: {1}

Category:
Patching

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192124
Info message from ZDT agent local invocation: {0}

Category:
Patching

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192125
Warning message from ZDT agent local invocation: {0}

Category:
Patching

Cause:
Warning generated while executing ZDT agent.

Action:
Review the warning message.

BEA-2192126
Error message from ZDT agent local invocation: {0}

Category:
Patching

Cause:
Operation failed while executing ZDT agent.

Action:
Review the cause based on the error message.

BEA-2192127
Exception message from ZDT agent local invocation: {0}

Category:
Patching

Cause:
Details of the cause are provided in the exception.

Action:
Take appropriate action based on the details provided in the exception.

BEA-2192128
Targeted application redeploy for "{0}" on partition "{1}"on server "{2}" during patching failed with an exception {3}.

Category:
Patching

Cause:
See the log for details about the cause of the failure.

Action:
Review the cause in the logs and address the reported issue. The partial completion of this operation may have left affected targets in an inconsistent state.

BEA-2192129
Rollout is being started on Coherence cluster "{0}" , but the cluster has only 2 managed servers or 2 machines. This can lead to probable data loss if during the rollout, the other server which is running fails.

Category:
Patching

Cause:
There are only 2 managed server belonging to the Coherence cluster.

Action:
The Coherence cluster must have atleast 3 managed servers, ideally belonging to 3 different machines, to prevent data loss during rollout.

BEA-2192130
ElasticitySyncCounter.loadCounterFromDisk caught an exception while trying to load persisted counter file from disk at [{0}]. Message: {1}

Category:
Patching

Cause:
An exception occurred while trying to load persisted file from disk

Action:
Review the cause in the logs and address the reported issue. The Elasticity service may remain enabled and affect the rollout operation.

BEA-2192300
The partition lifecycle operation "{0}" failed for partition "{1}".

Category:
Partition Lifecycle

Cause:
The partition lifecycle operation "{0}" failed for partition "{1}" with exception "{2}".

Action:
Try restarting the partition.

BEA-2192301
The resource group lifecycle operation "{0}" failed for resourceGroupName "{2}" of partition "{1}".

Category:
Partition Lifecycle

Cause:
The resource group lifecycle operation "{0}" failed for resourceGroupName "{2}" of partition "{1}" with exception "{2}".

Action:
Try restarting the resource group

BEA-2192302
The partition lifecycle operation "{0}" failed for partition "{1}".

Category:
Partition Lifecycle

Cause:
The partition lifecycle operation "{0}" failed for partition "{1}" with exception "{2}".

Action:
Check whether the targets for partition "{1}" are running.

BEA-2192303
The partition lifecycle operation "{0}" for partition "{1}" is initiated.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192304
The partition lifecycle operation "{0}" for partition "{1}" was successful.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192305
The partition lifecycle operation "{0}" for the untargeted partition "{1}" was successful.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192306
The resource group lifecycle operation "{0}" for resourceGroupName "{2}" of partition "{1}" was initiated.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192307
The resource group lifecycle operation "{0}" for resourceGroupName "{2}" of partition "{1}" was successful.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192308
The resource group lifecycle operation "{0}" for untargeted resourceGroupName "{2}" of partition "{1}" was successful.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192309
The partition "{0}" is already in the "{1}" state.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192310
The resource group "{0}" of partition "{1}" is already in the "{2}" state.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192311
The partition lifecycle operation "{1}" is in progress for partition "{0}".

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192312
The resource group lifecycle operation "{2}" for resource group "{0}" belonging to partition "{1}" is in progress.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192313
The partition lifecycle operation "{1}" on partition "{0}" is incompatible with the current state "{2}".

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192314
The resource group lifecycle operation "{2}" for resource group "{0}" belonging to partition "{1}" is incompatible with the current state "{3}".

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192315
The partition operation "{1}" for partition "{0}" failed with exception "{2}".

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192316
Performing an automatic HALT on partition "{1}" after operation "{0}" because there are no targeted active admin resource groups.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192317
Skipping BOOT for partition "{0}" because there are no targeted active admin resource groups.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192318
Graceful operation "{0}" on partition "{1}" timed out; converting to "{2}"

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192319
Partition lifecycle operation "{0}" initiated using partitionLifeCycleRuntimeMbean for partition "{1}" on servers "{2}"

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192320
The status of partition lifecycle sub task "{0}" for partition "{1}" is "{2}" on server "{3}"

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192321
The partition lifecycle sub task "{0}" for partition "{1}" failed on server "{2}" with exception "{3}"

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192322
The status of partition lifecycle task "{0}" for partition "{1}" is "{2}" on servers "{3}"

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192323
The partition lifecycle task "{0}" for partition "{1}" failed with exception "{2}"

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192324
The partition lifecycle operation "{0}" for the partition "{1}" is a no-op since the partition is already in expected state "{2}" in all the targeted servers

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192325
The resource group lifecycle operation "{0}" for the resource group "{1}" is a no-op since the resource group is already in expected state "{2}" in all the targeted servers

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192326
Resource group lifecycle operation "{0}" initiated using resourceGroupLifeCycleRuntimeMbean for resource group "{1}" on servers "{2}"

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192327
The status of resource group lifecycle sub task "{0}" for resource group "{1}" is "{2}" on server "{3}"

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192328
The resource group lifecycle sub task "{0}" for resource group "{1}" failed on server "{2}" with exception "{3}"

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192329
The status of resource group lifecycle task "{0}" for resource group "{1}" is "{2}" on servers "{3}"

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192330
The resource group lifecycle task "{0}" for resource group "{1}" failed with exception "{2}"

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192331
A partition forceRestart operation halted the partition "{0}" on this server but the corresponding runtime MBean remains.

Category:
Partition Lifecycle

Cause:
This is a warning message.

Action:
Monitor the system for unexpected behavior of the partition on this server.

BEA-2192332
Partition "{0}" is in state "{2}". The resource group "{1}" can not be transitioned to "{3}" state.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192333
Performing an automatic HALT on partition "{1}" after operation "{0}" because SHUTDOWN_TO_HALTED flag is True.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192334
An inconsistent state "{0}" and substate "{1}" were found; continuing with substate "{2}".

Category:
Partition Lifecycle

Cause:
The system uses separate remote messages to obtain the state and substate of a partition on a remote server. If between those two messages the state of the server or partition changes or the underlying network connection falters, the retrieved state and substate might be inconsistent with each other.

Action:
Make sure that the system actions following the substate substitution are what was intended.

BEA-2192335
Performing a RESUME instead of a START on partition "{0}" as the partition is in ADMIN state.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192336
Performing a RESUME instead of a START on resource group "{0}" of partition "{1}" as the resource group is in ADMIN state.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192337
Performing a RESUME instead of a START on resource group "{0}" as the resource group is in ADMIN state.

Category:
Partition Lifecycle

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192338
The partition lifecycle operation for partition "{0}" failed during server "{1}" start-up

Category:
Partition Lifecycle

Cause:
The partition lifecycle operation for partition "{0}" failed during server "{1}" start-up with exception "{2}"

Action:
Try invoking lifecycle operation on partition "{0}" to bring it back to correct state.

BEA-2192339
The partition lifecycle operation for partition "{0}" failed during server "{1}" shutdown

Category:
Partition Lifecycle

Cause:
The partition failed operation for partition "{0}" during server "{1}" shutdown with exception "{2}"

Action:
Try invoking lifecycle operation on partition "{0}" to bring it back to correct state.

BEA-2192400
JAX-RS OWSM configuration may not work: {0}

Category:
JAXRSClient

Cause:
This problem may be caused by an incorrect WebLogic class path.

Action:
No action is required.

BEA-2192500
Application MBean not initialized for application "{0}".

Category:
JAXRSIntegration

Cause:
The application was destroyed.

Action:
No action is required.

BEA-2192501
Cannot find URI for {0} resource class.

Category:
JAXRSIntegration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192502
Do not call JaxRsApplicationRuntimeMBean.setApplicationEnabled(boolean).

Category:
JAXRSIntegration

Cause:
This is an informational message. This is a deprecated API with no replacement.

Action:
Enable 'DebugRestJersey2Integration' to get the caller stack trace.

BEA-2192503
InitialContext not found. JAX-RS EJB support is not available.

Category:
JAXRSIntegration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192504
EJB component provider has not been initialized properly.

Category:
JAXRSIntegration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192505
An instance of EJB class {0} could not be looked up using a simple form name. Attempting to look up using the fully-qualified form name.

Category:
JAXRSIntegration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192506
Exception thrown when trying to look up actual handling method {0} for EJB type {1} using interface {2}.

Category:
JAXRSIntegration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192507
Class {0} has been bound by Jersey EJB component provider.

Category:
JAXRSIntegration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192508
The failure was: {0}

Category:
JAXRSIntegration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192509
Changing servlet class from {0} (web.xml) to {1}.

Category:
JAXRSIntegration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192510
Cannot add Jersey servlet for application class {0} because ApplicationPath annotation is not set on it.

Category:
JAXRSIntegration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2192511
The list of resource packages: {0}

Category:
JAXRSIntegration

Cause:
This is an informational message.

Action:
No action is required.

BEA-2194500
Initializing a Coherence cluster scoped to classloader {0} using {1}

Category:
CoherenceIntegration

Cause:
Initializing a Coherence cluster scoped to classloader {0} using {1}

Action:
No action is required.

BEA-2194501
Failed to initialize a Coherence cluster due to {0}

Category:
CoherenceIntegration

Cause:
Failed to initialize a Coherence cluster due to {0}

Action:
Take corrective action based on the exception details.

BEA-2194502
Shutting down a Coherence cluster scoped to classloader {0}

Category:
CoherenceIntegration

Cause:
Shutting down a Coherence cluster scoped to classloader {0}

Action:
No action is required.

BEA-2194503
Failed to shut down a Coherence cluster due to {0}

Category:
CoherenceIntegration

Cause:
Failed to shut down a Coherence cluster due to {0}

Action:
Take corrective action based on the exception details.

BEA-2194504
Deployed a GAR ({0}) without a CoherenceClusterSystemResourceMBean definition on this server. In most of the scenarios, a Coherence cluster must be created for applications to work properly.

Category:
CoherenceIntegration

Cause:
Deployed a GAR ({0}) without a CoherenceClusterSystemResourceMBean definition on this server.

Action:
Create a CoherenceClusterSystemResourceMBean appropriately and associate it with the server, or the cluster of which this server is a member. Only in some special cases, for example using Coherence Extend with TCMP disabled, a Coherence cluster may not be associated with a managed server.

BEA-2194505
Server {0} is configured with 'localhost' as the Unicast Listen Address. A generated Coherence WKA list will not operate correctly across multiple machines. This will result in an error if Coherence is run in Production mode.

Category:
CoherenceIntegration

Cause:
Server {0} is configured with 'localhost' as the Unicast Listen Address. When using Coherence WKA and not explicitly defining a WKA list, the configuration may not operate correctly across multiple machines. This will result in an error if Coherence is run in Production mode.

Action:
Explicitly define a Well Known Address (WKA) list for the Coherence cluster.

BEA-2194506
Could not find the JNDI resource [{0}] referenced by {1}.

Category:
CoherenceIntegration

Cause:
The JNDI resource [{0}] referenced by {1} could not be found.

Action:
Define the JNDI resource [{0}] referenced by {1}.

BEA-2194507
The Coherence cluster service failed to start or failed to join cluster due to {0} using {1}.

Category:
CoherenceIntegration

Cause:
The Coherence cluster service failed to start or failed to join cluster due to {0} using {1}.

Action:
Review the Coherence configuration for the cause of the exception.

BEA-2194508
Coherence configuration failed due to {0} using {1}.

Category:
CoherenceIntegration

Cause:
The Coherence configuration failed due to {0} using {1}.

Action:
Review the Coherence configuration for the cause of the exception.

BEA-2194509
The WeblogicCoherenceBean and CoherenceClusterParamsBean are not defined for the CoherenceClusterSystemResourceMBean {0}.

Category:
CoherenceIntegration

Cause:
The CohererenceClusterSystemResourceBean {0} needs to have an association with valid WeblogicCoherence and CoherenceCluster Beans.

Action:
Create a CoherenceClusterSystemResource MBean with the required associations.

BEA-2194510
While configuring the Coherence Cluster Service, the Server MBean or Server CoherenceMemberConfig MBean or both were not defined.

Category:
CoherenceIntegration

Cause:
The Server MBean or Server CoherenceMemberConfig MBean or both were not defined and thus will not be used when configuring the Coherence Cluster Service.

Action:
No action is required.

BEA-2194511
Server {0} is configured with 'localhost' as the Unicast Listen Address which is an error in Coherence Production mode. A generated Coherence WKA list will not operate correctly across multiple machines.

Category:
CoherenceIntegration

Cause:
Server {0} is configured with 'localhost' as the Unicast Listen Address resulting in an error when Coherence is in Production mode. When using Coherence WKA and not explicitly defining a WKA list, the configuration may not operate correctly across multiple machines.

Action:
Explicitly define a Well Known Address (WKA) list for the Coherence cluster.

BEA-2194512
While undeploying a GAR, the deployment module received an exception when closing files {0}.

Category:
CoherenceIntegration

Cause:
While undeploying a GAR, one or more files could not be closed due to {0}.

Action:
Review the exception and determine if there any file system issues for the referenced files.

BEA-2194513
Deployed an application ({0}) with Coherence*Web as session persistence type without a CoherenceClusterSystemResourceMBean definition on this server. Typically, a Coherence cluster must be created for this scenario to work properly.

Category:
CoherenceIntegration

Cause:
Deployed an application ({0}) with Coherence*Web as session persistence type without a CoherenceClusterSystemResourceMBean definition on this server.

Action:
Create a CoherenceClusterSystemResourceMBean appropriately and associate it with the server, or the cluster of which this server is a member. Only in some special cases, for example using Coherence Extend with TCMP disabled, a Coherence cluster may not be associated with a managed server.

BEA-2194514
There was an error creating Timer Manager for the Managed Server Level Coherence*Web Session Reaping Manager.

Category:
CoherenceIntegration

Cause:
TBD

Action:
TBD

BEA-2194515
There was an error during the Session Reaping process of the Coherence*Web Session Reaping Manager.

Category:
CoherenceIntegration

Cause:
TBD

Action:
TBD

BEA-2194801
The archive file name {0} specified for importPartition is null

Category:
DomainToPartition

Cause:
This is an internal WebLogic Server error.

Action:
Specify a valid archive file for importPartition

BEA-2194802
Partition name cannot be null, please specify a partition name.

Category:
DomainToPartition

Cause:
This is an internal WebLogic Server error.

Action:
Specify a name for the partition

BEA-2194803
A Path Service targeted to a cluster requires High Availability Policies set on that Cluster, so MigrationBasis must be set in the Cluster "{0}". If database is chosen as MigrationBasis, then DataSourceForAutomaticMigration must be set. When consensus leasing is chosen as MigrationBasis, all servers that belong to the cluster must have a machine set and node manager configured for that machine.

Category:
DomainToPartition

Cause:
This is an internal WebLogic Server error.

Action:
Configure the High Availability Policies for the Cluster "{0}".

BEA-2194804
A domain partition with the name "{0}" already exists. Please specify a name for the partition which is not already configured in the given domain.

Category:
DomainToPartition

Cause:
This is an internal WebLogic Server error.

Action:
Specify a name for the domain partition which is not already configured.

BEA-2194805
The domain archive "{0}" is empty, specify a valid domain archive for import operation.

Category:
DomainToPartition

Cause:
This is an internal WebLogic Server error.

Action:
Specify a valid domain archive for import operation.

BEA-2194806
The domain archive "{0}" and/or the associated json file is not compatible with the current version of importPartition. Please generate the archive using the current Domain To Partition Conversion Tool. If the generated json file is modified to remove the resource-group entries please correct it.

Category:
DomainToPartition

Cause:
This is an internal WebLogic Server error.

Action:
Supply a compatible domain archive for import partition operation.

BEA-2194807
Cannot find realm "{0}" in the domain configuration.

Category:
DomainToPartition

Cause:

Action:

BEA-2194808
The exiting virtual-target {0} is not for target {1}.

Category:
DomainToPartition

Cause:

Action:

BEA-2194809
Cannot create a virtual target with the name "{0}" as the server "{1}" is a member of the cluster "{2}"!

Category:
DomainToPartition

Cause:

Action:

BEA-2194810
Cannot add "{0}" to available targets of the domain partition as the server "{1}" is a member of the cluster "{2}".

Category:
DomainToPartition

Cause:

Action:

BEA-2194811
The target "{0}" of virtual-target "{1}" does not exist in the target domain.

Category:
DomainToPartition

Cause:

Action:

BEA-2194812
Cannot find Virtual Target "{0}" to add as an available target.

Category:
DomainToPartition

Cause:

Action:

BEA-2194813
Cannot find Virtual Target "{0}" to add as the default target.

Category:
DomainToPartition

Cause:

Action:

BEA-2194814
Virtual Target with the name "{0}" is not available, to set as target for the resource group "{1}"!

Category:
DomainToPartition

Cause:

Action:

BEA-2194815
Virtual Target with the name "{0}" is not one of the available targets in the partition "{1}"!

Category:
DomainToPartition

Cause:

Action:

BEA-2194816
Resource Group Template "{0}" already exists in the domain.

Category:
DomainToPartition

Cause:

Action:

BEA-2194817
JMS Server "{0}" is referencing a persistence store "{1}" with distribution policy 'Singleton', as it is hosting one or more standalone destinations. However the same persistence store is referenced by SAF Agent "{2}", which requires the persistence store to have distribution policy 'Distributed'. This conflict is not allowed, so JMS Server and SAF Agent should not refer the same persistence store.

Category:
DomainToPartition

Cause:

Action:

BEA-2194818
The "{0}" element in the json generated by the Domain TO Partition Conversion Tool is not an JSON Array. If the json file is modified before import, please correct the issue and try import again.

Category:
DomainToPartition

Cause:

Action:

BEA-2194819
Cannot add the Virtual Target "{0}" to available targets of the domain partition as the server "{1}" is a member of the cluster "{2}".

Category:
DomainToPartition

Cause:

Action:

BEA-2194820
The destination for writing the imported application "{0}" already exists at {1}.

Category:
DomainToPartition

Cause:

Action:

BEA-2194821
The imported zip file does not contain the application plan at "{0}".

Category:
DomainToPartition

Cause:
TBD

Action:
TBD

BEA-2194822
The imported zip file does not contain the application/library source at "{0}".

Category:
DomainToPartition

Cause:

Action:

BEA-2194823
The destination for writing the imported plan for application "{0}" already exists at {1}.

Category:
DomainToPartition

Cause:

Action:

BEA-2194824
Import of "{1}" of type "{0}" is excluded in the json file, an excluded resource won't be available in the partition.

Category:
DomainToPartition

Cause:
The resource is excluded in the json file generated by Domain To Partition Conversion Tool, before importing to the partition.

Action:
Manually configure the resource appropriately.

BEA-2194825
Partition "{0}" already contains a default target with the name "{1}".

Category:
DomainToPartition

Cause:

Action:

BEA-2194826
Cannot find/set JDBCStore "{0}" to JMS Server "{1}".

Category:
DomainToPartition

Cause:

Action:

BEA-2194827
Removing the target "{1}" from the subdeployment "{0}", to retain the first target for the subdeployment.

Category:
DomainToPartition

Cause:

Action:

BEA-2194828
Modifying the distribution policy to 'Singleton' and the migration policy to 'Always' of the persistent store "{0}" referenced by the Path Service "{1}".

Category:
DomainToPartition

Cause:

Action:

BEA-2194829
Path Service "{0}" in the source domain was pointing to default store. So creating a file store with the name "{1}" under Resource Group / Resource Group Template "{2}" as a path service without a valid store is not supported in a partitioned environment.

Category:
DomainToPartition

Cause:

Action:

BEA-2194830
The importPartition operation failed to create the report.

Category:
DomainToPartition

Cause:

Action:

BEA-2194831
The importPartition operation completed.

Category:
DomainToPartition

Cause:

Action:

BEA-2194832
The activation of importPartition failed with the error - {0}

Category:
DomainToPartition

Cause:

Action:

BEA-2194833
Error creating the JDBC Store "{0}", cannot find and set JDBC SystemResource "{1}"

Category:
DomainToPartition

Cause:

Action:

BEA-2194834
The JDBC Store "{0}" in the source domain does not have an associated JDBC System Resource. So this JDBC Store won't be created in the target domain partition. Any reference to this JDBC Store by a JMS Server or a SAF Agent or a Path Service will result in a validation exception due to unresolved reference in the configuration (config.xml).

Category:
DomainToPartition

Cause:

Action:

BEA-2194835
The Uniform Distributed Topic "{0}" in JMS Module "{1}" is configured to use the forwarding policy 'Replicated'(the default). This configuration is not supported when importing this domain to a partition, so the forwarding policy will be changed to 'Partitioned'.

Category:
DomainToPartition

Cause:

Action:

BEA-2194836
The subdeployment "{0}" in JMS Module "{1}" is targeted to "{2}" of type "{3}". This configuration is not supported. Subdeployments when not targeted to a JMS Server or a SAF Agent, will be left untargeted and any resources that reference that subdeployment will not be deployed.

Category:
DomainToPartition

Cause:

Action:

BEA-2194837
The subdeployment "{0}" in JMS Module "{1}" is targeted to "{2}" of type "{3}" and "{2}" is associated with a specific server in cluster "{4}" via a target of "{5}" of type "{6}". Partition scoped JMS destinations do not support targeting a particular Server or Migratable Target, so, after import, this subdeployment will be targeted to a JMS Server or a SAF Agent with an effective target of a Cluster, the destination runtime will therefore be hosted on a single random server in the cluster, or across all members of the cluster depending on its distribution policy and the server hosting the destination may change after failures or restarts.

Category:
DomainToPartition

Cause:

Action:

BEA-2194838
The subdeployment "{0}" in JMS module "{1}" does not have any valid target. After import, any JMS destination that refer this subdeployment will not be deployed.

Category:
DomainToPartition

Cause:

Action:

BEA-2194839
Unable to undo the changes which are not activated. Cause: {0}

Category:
DomainToPartition

Cause:

Action:

BEA-2194840
JMS Server "{0}" is found to be hosting one or more standalone destinations as well as Uniform Distributed Destinations using subdeployments. As the required Distribution Policy to host these destinations conflict, this is not allowed by Domain To Partition Conversion Tool(D-PCT).

Category:
DomainToPartition

Cause:

Action:

BEA-2194841
JMS Server "{0}" is found to be hosting one or more standalone destinations as well as Foregin Server using subdeployments. As the required Distribution Policy to host these destinations conflict, this is not allowed by D-PCT.

Category:
DomainToPartition

Cause:

Action:

BEA-2194842
The library file "{0}" available at "{1}" is used; the source library is ignored.

Category:
DomainToPartition

Cause:
The require-exact-version attribute available at the json file was set to "false" for the library "{0}" and hence the version of the library available at the target domain is being used.

Action:
Set the require-exact-version attribute in the json need to be set to "true" to get the same source file library before import.

BEA-2194843
The target "{0}" is invalid or not found in the target domain. Please provide a JMSServer/SAF-Agent target name that exists.

Category:
DomainToPartition

Cause:

Action:

3
BRW-15000 to BRW-16976

BRW-15000
Internal error in Query Builder error handler

Category:
Other

Cause:
Error handler could not be started.

Action:
Contact support.

BRW-15001
{1}

Category:
Other

Cause:
Message not found

Action:
Check Query Builder directory in Oracle Home for message file.

BRW-15002
Out of memory!

Category:
Other

Cause:
Out of memory.

Action:
Save documents and restart Query Builder.

BRW-15003
Invalid file name: {1}

Category:
Other

Cause:
User entered an invalid file name (for example, too many characters).

Action:
Enter a new, valid file name.

BRW-15004
Internal error ({1}:{2})

Category:
Other

Cause:
Internal Error Occurred -- Query Builder is in an unreliable state.

Action:
Contact support.

BRW-15005
No file name specified

Category:
Other

Cause:
User did not enter a filename in the Export Data Dialog.

Action:
Enter a filename.

BRW-15006
Unable to DESCRIBE data table

Category:
Data

Cause:
Internal message.

Action:
Contact support.

BRW-15007
SQL statement is too complex to display.

Category:
Other

Cause:
Exceeded the edit buffer size on MSWINDOWS.

Action:
Exclude some columns from the query to reduce the SQL statement size.

BRW-15009
Insufficient privileges to login through Query Builder

Category:
Other

Cause:
Connect privileges are disabled in the SYSTEM.BROWSER_PROFILE table.

Action:
Contact your DBA.

BRW-15010
Insufficient privileges to edit schema through Query Builder

Category:
Other

Cause:
Schema Editing privileges are not enabled in the SYSTEM.BROWSER_PROFILE table.

Action:
Contact your DBA.

BRW-15011
Insufficient privileges to edit data through Query Builder

Category:
Data

Cause:
Data Editing privileges are not enabled in the SYSTEM.BROWSER_PROFILE table.

Action:
Contact your DBA.

BRW-15012
Cannot edit schema with DICTIONARY=ENDUSER command-line option

Category:
Other

Cause:
Query Builder cannot invoke the Schema Builder when DICTIONARY=ENDUSER.

Action:
Run Query Builder with the DICTIONARY=NATIVE command line option.

BRW-15013
Insufficient privileges to edit End User Layer through Query Builder

Category:
Other

Cause:
Meta-data Editing privileges are not enabled in the SYSTEM.BROWSER_PROFILE table.

Action:
Contact your DBA.

BRW-15025
Unable to load list of database roles

Category:
Other

Cause:
Schema internal error in loading list of database roles.

Action:
Contact support if this is not expected.

BRW-15065
Syntax error

Category:
Other

Cause:
User typed a formula incorrectly.

Action:
Re-type the expression.

BRW-15066
Expression is too complex

Category:
Other

Cause:
Expression is too complex.

Action:
Simplify the expression.

BRW-15068
Invalid function: {1}

Category:
Other

Cause:
User entered an invalid function name.

Action:
Specify a valid function.

BRW-15069
Invalid column: {1}

Category:
Other

Cause:
User entered an invalid column name.

Action:
Enter a valid column name.

BRW-15070
Invalid table: {1}

Category:
Other

Cause:
User entered an invalid table name.

Action:
Enter a valid table name.

BRW-15071
Invalid owner: {1}

Category:
Other

Cause:
User entered an invalid user or business area name.

Action:
Enter a valid user or business area name.

BRW-15072
Invalid condition

Category:
Other

Cause:
User entered an invalid condition.

Action:
Delete the condition and enter a valid condition.

BRW-15073
Invalid expression

Category:
Other

Cause:
User entered an invalid expression (usually blank).

Action:
Enter a valid expression.

BRW-15074
Invalid use of reserved word {1}

Category:
Other

Cause:
User used a reserved word as an identifier.

Action:
Identifiers cannot be reserved words. Refer to the help or documentation for details.

BRW-15075
Invalid number of arguments to function {1}

Category:
Other

Cause:
User entered too few or too many arguments for the given function.

Action:
Enter the appropriate arguments. Refer to the help or documentation for details.

BRW-15077
Ambiguous name: {1}

Category:
Other

Cause:
User entered an ambiguous column name.

Action:
Enter a specific column name, include any qualifiers.

BRW-15078
Redefinition of name: {1}

Category:
Other

Cause:
User redefined a column or data table using a name that already exists.

Action:
Define the column or table using a new name.

BRW-15079
No columns selected in query

Category:
Other

Cause:
Query was either built or entered with no displayed columns.

Action:
Select columns before re-executing the query.

BRW-15080
No tables specified in query

Category:
Other

Cause:
User entered a query without specifying any tables.

Action:
Select tables before re-executing the query.

BRW-15081
START WITH requires CONNECT BY

Category:
Other

Cause:
SQL statement contained a START WITH clause without a CONNECT BY clause.

Action:
Specify a CONNECT BY clause if using START WITH.

BRW-15082
PRIOR requires CONNECT BY

Category:
Other

Cause:
SQL statement contained a PRIOR clause without a CONNECT BY clause.

Action:
Specify a CONNECT BY clause if using PRIOR.

BRW-15083
Bad argument type to function {1}

Category:
Other

Cause:
User entered the wrong argument type for the function.

Action:
Enter the correct argument type.

BRW-15084
Unterminated comment

Category:
Other

Cause:
Buffer being read in has an unterminated C-type comment in it.

Action:
Edit the file (see that it terminates correctly), and reopen from Query Builder.

BRW-15085
Circular reference detected in defined column

Category:
Other

Cause:
Modification of a defined column has led to a circular reference.

Action:
Redefine the column so that it does not refer to itself in its own definition.

BRW-15086
Arguments to a correlated subquery function must be columns

Category:
Other

Cause:
A complex argument was given, such as avg (sal, deptno*2).

Action:
Specify only valid columns, not expressions, in the subquery.

BRW-15087
Invalid location: {1}

Category:
Other

Cause:
User entered an invalid database location for a table.

Action:
Enter a valid database location.

BRW-15088
Ambiguous table: {1}

Category:
Other

Cause:
User entered an ambiguous data table name (more than one table uses this name).

Action:
User must further qualify the data table. Refer to the help or

BRW-15089
Only one PRIOR operator allowed on an expression

Category:
Other

Cause:
User typed 2 or more PRIOR clauses in an expression.

Action:
Remove one of the PRIOR clauses.

BRW-15090
The name {1} is already in use

Category:
Other

Cause:
User entered a name that was already being used.

Action:
Enter a new name.

BRW-15091
Invalid name: {1}

Category:
Other

Cause:
User entered an invalid name (with spaces or unprintable chars).

Action:
Enter a new name.

BRW-15092
Bad usage of outer relationship

Category:
Other

Cause:
User specified an outer relationship on a non-column element.

Action:
Outer relationships are only valid for columns.

BRW-15093
Invalid number of elements in corresponding record

Category:
Other

Cause:
User entered two records with different numbers of elements.

Action:
Reenter the condition.

BRW-15094
Group function is nested too deeply

Category:
Other

Cause:
User entered a double(triple) aggregate condition(expression).

Action:
Simplify aggregate condition/expression.

BRW-15096
Table name conflicts with {1}, renamed to {2}

Category:
Other

Cause:
When opening a query, a table alias name conflicts with a new column.

Action:

BRW-15097
Name conflicts with {1}, renamed to {2}

Category:
Other

Cause:
When loading a saved query, an alias name conflicts with a new column.

Action:

BRW-15098
Duplicate table {1} in FROM clause

Category:
Other

Cause:
Data table appears more than once in FROM clause (without an alias).

Action:
Remove the duplicate data tables in the FROM clause.

BRW-15099
Subquery returns incorrect number of values

Category:
Other

Cause:
Subquery returns either too many or too few values.

Action:
Reenter condition.

BRW-15100
Correlated expressions are not allowed here

Category:
Other

Cause:
User entered a correlated expression outside a condition.

Action:
Reenter the condition/expression.

BRW-15101
Table alias cannot be reused in the same FROM clause: {1}

Category:
Other

Cause:
User tried to use an alias in the same FROM clause it was defined in.

Action:
Remove the reference to the alias.

BRW-15102
Too many elements in record

Category:
Other

Cause:
User entered a record with more than 254 elements.

Action:
Reduce the number of elements--split the condition into an OR.

BRW-15103
Unnamed SELECT statement in FROM clause

Category:
Other

Cause:
SQL contained a query in the FROM clause without name.

Action:
Add the query name and reparse.

BRW-15110
Invalid number or precision exceeded: {1}

Category:
Other

Cause:
Non-numeric input or the number exceeded this column's precision.

Action:
Re-enter a valid number and precision.

BRW-15111
Invalid date: {1}

Category:
Other

Cause:
Could not format using the columns format mask or either default mask.

Action:
Re-enter a valid format mask.

BRW-15112
Entry exceeds the size limit for this column: {1}

Category:
Other

Cause:
User entered a string longer than the limit for this column.

Action:
Enter a shorter string.

BRW-15113
Not all parameters have been specified

Category:
Other

Cause:
User attempted to execute a query without defining all parameters

Action:
Specify parameters or exclude parameterized expressions and retry.

BRW-15114
Parameters can only be constant expressions

Category:
Other

Cause:
User attempted to enter a parameter value that depended on a column value.

Action:
Specify a valid parameter, one that does not depend on the value in a column.

BRW-15115
Bad usage of parameter {1}

Category:
Other

Cause:
User entered a parameter name for a column or table.

Action:
Specify a valid parameter.

BRW-15116
Invalid parameter name {1}

Category:
Other

Cause:
User entered an invalid parameter name.

Action:
Specify a valid parameter name.

BRW-15117
Invalid parameter {1}

Category:
Other

Cause:
User entered an invalid parameter.

Action:
Specify valid parameter.

BRW-15128
Parser internal error: {1}

Category:
Other

Cause:
Internal error in the parser/scanner.

Action:
Contact support.

BRW-15129
Defined column {1} cannot be used in correlated subquery function

Category:
Other

Cause:
Use of derived columns (DQ4) in correlated subquery.

Action:
Remove that argument from the correlated subquery.

BRW-15130
Query execution failed

Category:
Other

Cause:
Database access error.

Action:
Check database error and rerun query.

BRW-15131
Invalid relational operator

Category:
Other

Cause:
User applied an invalid operator to a condition.

Action:
Enter a valid operator.

BRW-15132
FROM clause was not found where expected

Category:
Other

Cause:
Encountered no FROM clause or GROUP/HAVING clause before a FROM clause.

Action:
Edit SQL statement.

BRW-15133
FROM clause was found without corresponding SELECT clause

Category:
Other

Cause:
Encountered FROM clause before SELECT clause.

Action:
Edit SQL statement.

BRW-15135
Condition cannot be changed

Category:
Other

Cause:
user attempted to change the top condition in Schema Builder.

Action:
Perform the operation on the children conditions.

BRW-15136
SQL contains set operators

Category:
Other

Cause:
Set operations are not supported.

Action:
Run the query in SQLPlus.

BRW-15137
Unable to generate names for complex expressions

Category:
Other

Cause:
Encountered expressions without names when opening a SQL file.

Action:
Define Names for columns in the .sql file.

BRW-15138
CONNECT BY clause existed, and was ignored

Category:
Other

Cause:
Connect By is not supported at this (top) level.

Action:
Run the query in SQLPlus, if results of CONNECT BY were desired.

BRW-15139
Cannot ungroup condition

Category:
Other

Cause:
Attempt to ungroup top condition.

Action:
This operation is not supported.

BRW-15141
Query table cannot contain parameters

Category:
Other

Cause:
Encountered one or more parameters when creating a view.

Action:
Exclude parameters from query or ignore.

BRW-15142
Two or more columns have the same name: {1}

Category:
Other

Cause:
Encountered duplicate column names when creating view.

Action:
Use the Define command to rename duplicate columns.

BRW-15143
{1} is already a display column

Category:
Other

Cause:
User tried to specify a duplicate display column.

Action:
If duplicate column is desired, define a new name for it and re-display it.

BRW-15144
{1} is already a sort column

Category:
Other

Cause:
User tried to specify a duplicate sort column.

Action:
If duplicate column is desired, define a new name for it and re-sort.

BRW-15145
{1} is already a group column

Category:
Other

Cause:
user tried to specify a duplicate group column.

Action:
If duplicate column is desired, define a new name for it and re-group.

BRW-15146
Internal error in opening query

Category:
Other

Cause:
Internal error in opening query.

Action:
Contact support.

BRW-15147
Internal error in saving query

Category:
Other

Cause:
Internal error in saving query.

Action:
Contact support.

BRW-15148
Relationship must be between compatible data types/size

Category:
Data

Cause:
User tried to relate two columns with incompatible data types.

Action:
Relate only compatible datatypes. Refer to the help or documentation for details.

BRW-15150
Cannot define a self-relationship

Category:
Other

Cause:
User tried to define a relationship within a data table.

Action:
Alias the data table and then define the relationship.

BRW-15151
User-defined relationship already exists

Category:
Other

Cause:
User tried to define a relationship that already exists.

Action:
No action required.

BRW-15152
Illegal column in defined relationship

Category:
Other

Cause:
User specified an illegal expression when defining a relationship.

Action:
Retype in a new column.

BRW-15153
Table alias name cannot end with _A<number>

Category:
Other

Cause:
Illegal alias name.

Action:
Input a new name that does not end with _A<number>.

BRW-15154
Cannot remove database relationship

Category:
Other

Cause:
User tried to remove data dictionary relationship.

Action:
Only user-defined relationships can be deleted.

BRW-15155
The following documents may have been affected:{1}

Category:
Other

Cause:
A saved query was being used as a data table in other query documents.

Action:
If you change or delete this query, you will affect these other queries.

BRW-15156
Cannot include table with the same name as the query

Category:
Other

Cause:
User attempted to include data table D in query document D.

Action:
Rename the query before including this table.

BRW-15157
Cannot sort, group, or break on LONG columns

Category:
Other

Cause:
Trying to sort, group or break on LONG column type.

Action:
Cancel the operation. Oracle does not support this.

BRW-15158
Cannot sort, group, or break on RAW columns

Category:
Other

Cause:
Trying to sort, group or break on RAW column type.

Action:
Cancel the operation. Oracle does not support this.

BRW-15159
Cannot display LONG columns from remote databases

Category:
Other

Cause:
Trying to include LONG column type from remote database data table.

Action:
Cancel the operation. Oracle does not support this.

BRW-15160
Maximum number ({1}) of columns exceeded

Category:
Other

Cause:
User exceeded maximum number of display/group/sort columns supported.

Action:
Delete some unwanted columns, then re-include what you need.

BRW-15161
Error in opening {1} display column(s)

Category:
Other

Cause:
Unable to open DISPLAY column because database has changed since save.

Action:
This column may have changed or no longer exist in the database.

BRW-15162
Error in opening {1} sort column(s)

Category:
Other

Cause:
Unable to open SORT column because database has changed since save.

Action:
This column may have changed or no longer exist in the database.

BRW-15163
Error in opening {1} group column(s)

Category:
Other

Cause:
Unable to open GROUP column because database has changed since save.

Action:
This column may have changed or no longer exist in the database.

BRW-15164
Error in opening {1} break column(s)

Category:
Other

Cause:
Unable to open BREAK column because database has changed since save.

Action:
This column may have changed or no longer exist in the database.

BRW-15165
Maximum number ({1}) of break columns exceeded

Category:
Other

Cause:
User exceeded the maximum number of break columns supported.

Action:
Delete some unwanted break columns, then re-include what you need.

BRW-15166
Error in opening {1} condition(s)

Category:
Other

Cause:
Unable to open conditions because database has changed since save.

Action:
Tables or columns used in this condition may no longer exist in the database.

BRW-15167
Alias must be {1} bytes or less: {2}

Category:
Other

Cause:
alias name too long.

Action:
Try typing in an alias less than or equal to 30 bytes long.

BRW-15168
Cannot group on aggregate expression

Category:
Other

Cause:
Tried to group on an aggregate expression.

Action:
Group on another expression.

BRW-15169
{1} has already been included as a break column

Category:
Other

Cause:
User tried to specify a duplicate break column.

Action:
If duplicate column is desired, define a new name for it and re-break.

BRW-15170
Invalid Constraint for table {1}

Category:
Other

Cause:
User entered an invalid constraint for the selected table.

Action:
Reenter constraint.

BRW-15171
Invalid Constraint for table column {1}

Category:
Other

Cause:
User entered an invalid constraint for the selected column.

Action:
Reenter constraint.

BRW-15172
Subqueries are not allowed in Constraints

Category:
Other

Cause:
User entered an invalid constraint.

Action:
Reenter constraint.

BRW-15173
Aggregate conditions are not allowed in Constraints

Category:
Other

Cause:
User entered an invalid constraint.

Action:
Reenter constraint.

BRW-15174
Constraints can only be on one table

Category:
Other

Cause:
User entered an invalid constraint.

Action:
Reenter constraint.

BRW-15175
Table not loaded because all columns are hidden

Category:
Other

Cause:
All columns are hidden. At least one column needs to be displayed.

Action:
Use the Browser Administrator Utility to display hidden columns.

BRW-15188
Query returns 1 row

Category:
Other

Cause:
Status message for 1-row Query Count.

Action:
No action required.

BRW-15189
Query returns {1} rows

Category:
Other

Cause:
Status message for n-row Query Count.

Action:
No action required.

BRW-15190
Unable to count without executing; Query returns <= {1} row(s)

Category:
Other

Cause:
Status message for n-row Query Count Distinct.

Action:
No action required.

BRW-15192
Illegal format '{1}' for column '{2}'

Category:
Other

Cause:
User typed an unrecognizable format for a display column.

Action:
Try another format.

BRW-15193
Illegal format

Category:
Other

Cause:
User typed an unrecognizable format for a display column

Action:
Try another format.

BRW-15195
Incompatible column type in relationship: {1}

Category:
Other

Cause:
Trying to create illegal relationship.

Action:
Column types are incompatible. Refer to the help or documentation for details.

BRW-15196
Error in opening {1} table(s)

Category:
Other

Cause:
Unable to open data tables because database was modified or object does not exist.

Action:
Check your connect string (or contact your DBA).

BRW-15197
Error in restoring position for {1} column(s)

Category:
Other

Cause:
Unable to reposition column because database was modified or object does not exist.

Action:
Check your connect string (or contact your DBA).

BRW-15198
Error in restoring join: {1}

Category:
Other

Cause:
Unable to restore link during open because database was modified or object does not exist.

Action:
Check your connect string (or contact your DBA).

BRW-15199
Error in restoring inclusion state for join: {1}

Category:
Other

Cause:
Unable to set the inclusion state during open because database was modified or object does not exist.

Action:
Check your connect string (or contact your DBA).

BRW-15200
Error in restoring outer join state for join: {1}

Category:
Other

Cause:
Unable to set the outer join during open because database was modified or object does not exist.

Action:
Check your connect string (or contact your DBA).

BRW-15258
Invalid document name: {1}

Category:
Other

Cause:
User entered an invalid document name.

Action:
Enter a valid document name.

BRW-15259
Document exceeds 64K size limit

Category:
Other

Cause:
User attempted to save/open a document larger than 64K.

Action:
Reduce size of document.

BRW-15260
Document {1} does not exist

Category:
Other

Cause:
User specified a nonexistent document.

Action:
Specify another document.

BRW-15261
Document {1} already exists

Category:
Other

Cause:
User tried to save under the name of an existing document.

Action:
Specify another document name or delete the existing document.

BRW-15262
Multiple documents named {1}

Category:
Other

Cause:
Multiple documents with same name exist.

Action:
Delete all but one.

BRW-15263
Database object {1} already exists

Category:
Other

Cause:
User tried to save under the name of an existing object.

Action:
Specify another document name.

BRW-15264
Table {1} does not exist

Category:
Other

Cause:
Data Table view corresponding to a saved document has been removed.

Action:
Re-save the document (it no longer exists as a query view).

BRW-15265
Table {1} has been removed or modified

Category:
Other

Cause:
Data Table view corresponding to a saved document has been modified.

Action:
Re-save the document.

BRW-15266
File {1} does not exist

Category:
Other

Cause:
User specified a nonexistent file.

Action:
Specify another file.

BRW-15267
File {1} already exists

Category:
Other

Cause:
User tried to save under the name of an existing file.

Action:
Specify another file name.

BRW-15268
Unable to open file {1}

Category:
Other

Cause:
I/O core was unable to open a file.

Action:
Specify another file.

BRW-15269
Unable to lock file {1}

Category:
Other

Cause:
I/O core was unable to lock a file.

Action:
Specify another file.

BRW-15270
Error reading file {1}

Category:
Other

Cause:
Operating system error or file was not of the correct format.

Action:
Specify another file.

BRW-15271
Error writing file {1}

Category:
Other

Cause:
Operating system error or I/O core error.

Action:
Retry operation.

BRW-15272
Obsolete Query Builder document {1}

Category:
Other

Cause:
User attempted to open an old unsupported document.

Action:
Specify another document.

BRW-15273
File {1} is not a Query Builder file

Category:
Other

Cause:
User attempted to open a non-Browser file.

Action:
Specify another file to open.

BRW-15274
File {1} is not a valid SQL file

Category:
Other

Cause:
User attempted to import an invalid SQL file.

Action:
Specify another file to import.

BRW-15275
No data to export or print

Category:
Data

Cause:
User attempted to export or print a query (or region) with no data.

Action:
Specify another region; execute query; change query.

BRW-15277
Unable to overwrite current table {1}

Category:
Other

Cause:
Error in trying to delete/rename old data table in save.

Action:
Fix problem with data table and re-save.

BRW-15278
Document saved, but view {1} could not be created

Category:
Other

Cause:
The query is not a valid view. It has been saved, but not as a database view.

Action:
Redefine query as a valid view, or ignore (query will be saved, but not as a view).

BRW-15279
'{1}' is not a recognized SQL literal

Category:
Other

Cause:
User attempted to import a non-SQLPlus file.

Action:
Specify another file to import.

BRW-15320
Internal I/O core error ({1}, line {2})

Category:
Other

Cause:
Internal State is invalid.

Action:
Contact support.

BRW-15321
Resource not found ({1}).

Category:
Other

Cause:
Resource names do not match Browser code (or file is corrupted).

Action:
Get a correct version of the Browser resource file.

BRW-15322
Resource file not found.

Category:
Other

Cause:
directory structure incorrect, or file is missing for some reason.

Action:
Locate the resource file (check NLS_LANG file name).

BRW-15323
Query already open in current application ({1})

Category:
Other

Cause:
User attempted to open multiple queries with the same name.

Action:
Specify another file.

BRW-15324
Unable to start up windowing system

Category:
Other

Cause:
Incorrect/missing environment variables (for example, DISPLAY, APIPATH).

Action:
All required environment variables must be set correctly.

BRW-15337
Maximum columns in index is {1}

Category:
Other

Cause:
Maximum columns in index reached.

Action:
Create/modify index with less columns.

BRW-15338
Cannot remove/modify index used to enforce unique/primary key

Category:
Other

Cause:
User tried to remove/modify the index used to enforce unique/primary key.

Action:
First remove/modify primary key or unique key.

BRW-15339
Cannot create, modify, or remove index on synonyms

Category:
Other

Cause:
User tried to create, modify, or remove the index for a synonym

Action:
Create, modify, or remove index from base table instead.

BRW-15340
Cannot modify constraints for a synonym.

Category:
Other

Cause:
Modifying constraints of a synonym is not allowed.

Action:
Modify constraint of base data table instead.

BRW-15341
Base table can only be modified after committing duplicated table

Category:
Other

Cause:
User tried to modify a base data table that has been duplicated.

Action:
Commit the duplicated table first.

BRW-15342
Unable to find snapshot information

Category:
Other

Cause:
This database does not support snapshots (or database error).

Action:
Check that you have a snapshot dictionary table.

BRW-15343
Insufficient privileges to use DICTIONARY=NATIVE

Category:
Other

Cause:
You do not have access privileges to use the NATIVE dictionary.

Action:
Use DICTIONARY=ENDUSER instead. This can be specified on the command line.

BRW-15344
Insufficient privileges to use DICTIONARY=ENDUSER

Category:
Other

Cause:
You do not have access privileges to use the ENDUSER dictionary

Action:
Use DICTIONARY=NATIVE instead. This can be specified on the command line.

BRW-15345
Cannot load MVIEW$_ or SNAP$_ tables. Load snapshot instead.

Category:
Other

Cause:
Trying to import sql which uses MVIEW$_ or SNAP$_ of snapshot.

Action:
Load the snapshot itself instead.

BRW-15346
Cannot REVOKE privileges you did not grant

Category:
Other

Cause:
User trying to revoke privileges that he/she did not grant.

Action:
The user who grants the privileges should revoke those privileges.

BRW-15347
Cannot grant EXECUTE privilege on tables

Category:
Other

Cause:
Trying to grant EXECUTE privilege on tables.

Action:
EXECUTE privilege is only allowed on packages.

BRW-15348
ALTER, INDEX, REFERENCES, or EXECUTE privileges not allowed on views

Category:
Other

Cause:
Trying to grant ALTER, INDEX, REFERENCES, or EXECUTE on views.

Action:
This is not allowed.

BRW-15349
Only SELECT privilege is allowed on snapshots

Category:
Other

Cause:
SELECT privilege is only allowed for snapshots.

Action:
Grant only SELECT privilege on snapshots.

BRW-15350
No privileges is allowed for synonyms

Category:
Other

Cause:
Trying to grant privileges on synonyms.

Action:
This is not allowed.

BRW-15351
Insufficient privileges. Operation denied.

Category:
Other

Cause:
User try to perform an operation without sufficient privileges.

Action:
Try again after obtaining proper privileges from your DBA.

BRW-15352
Cannot remove existing table columns

Category:
Other

Cause:
Trying to remove an existing table column.

Action:
This operation is not supported by the database.

BRW-15354
Cannot rename existing table columns

Category:
Other

Cause:
Trying to rename an existing data table column.

Action:
This action is not supported by the database.

BRW-15355
Cannot change indexed column datatype to LONG

Category:
Other

Cause:
Trying to change an indexed column type to a LONG datatype.

Action:
This action is not supported by the database.

BRW-15356
Removed tables cause referenced synonyms to be removed

Category:
Other

Cause:
User removed some data tables that have synonyms refer to them.

Action:
None. This is a warning that synonyms are removed automatically.

BRW-15357
Error in removing constraint {1}

Category:
Other

Cause:
Error in removing constraint.

Action:
Try again.

BRW-15358
Error in enabling/disabling constraints for {1}

Category:
Other

Cause:
Error in enabling/disabling constraints.

Action:
Try again.

BRW-15359
Cannot disable a key referred by a newly created FOREIGN key

Category:
Other

Cause:
Trying to disable a primary or unique key that a foreign key depends upon.

Action:
Commit the foreign key first, then disable.

BRW-15360
Foreign key refers to disabled PRIMARY/UNIQUE key {1}

Category:
Other

Cause:
Foreign key refers to a disabled primary key.

Action:
Enable primary key for the foreign key to be created successfully.

BRW-15361
Error in creating PRIMARY/UNIQUE constraints for {1}

Category:
Other

Cause:
Error in creating PRIMARY/UNIQUE constraints.

Action:
Try again.

BRW-15362
Error in creating FOREIGN constraints for {1}

Category:
Other

Cause:
Error in creating FOREIGN constraints.

Action:
Try again.

BRW-15363
Error in creating CHECK constraints for {1}

Category:
Other

Cause:
Error in creating CHECK constraints.

Action:
Try again.

BRW-15364
Length of VARCHAR2 column must be between {1} and {2}

Category:
Other

Cause:
Illegal range for length of VARCHAR2 column.

Action:
Specify a legal length parameter.

BRW-15365
Non-unique INDEX column cannot have PRIMARY/UNIQUE constraint

Category:
Other

Cause:
User tried to create PRIMARY/UNIQUE constraints on a non-unique index.

Action:
Remove the index, and recreate as a unique index.

BRW-15366
PRIMARY/UNIQUE column cannot have non-unique index

Category:
Other

Cause:
Trying to create a non-unique index with PRIMARY/UNIQUE columns.

Action:
Set the index to UNIQUE. Remove and recreate.

BRW-15367
Cannot rename snapshots

Category:
Other

Cause:
User tried to rename a snapshot

Action:
This is not allowed.

BRW-15368
Error in altering snapshot {1}

Category:
Other

Cause:
Internal error.

Action:
Try again.

BRW-15369
Error in creating snapshot {1}

Category:
Other

Cause:
Internal error.

Action:
Try again.

BRW-15370
Cannot add columns to a table duplicated with data

Category:
Data

Cause:
Trying to add columns to an uncommitted data table (duplicated with data).

Action:
Commit first, then add columns

BRW-15371
Comment too long (max {1} bytes)

Category:
Other

Cause:
The comment specified for the data table or column is too long.

Action:
Shorten the comment.

BRW-15372
Cannot set comment for synonym

Category:
Other

Cause:
User tried to create a comment for a synonym.

Action:
Create the comment on the table or view instead.

BRW-15373
Cannot create primary, unique, foreign key, or index on LONG columns

Category:
Other

Cause:
These operations cannot be performed on LONG columns.

Action:
Do not attempt to perform this operation.

BRW-15374
Cannot remove tables that are referenced

Category:
Other

Cause:
User tried to remove a table with primary or unique keys that are referenced.

Action:
Remove referencing table first.

BRW-15375
Cannot create index through database link

Category:
Other

Cause:
User tried to create an index through a database link.

Action:
Login directly then create index.

BRW-15376
Cannot create constraint through database link

Category:
Other

Cause:
User tried to create a constraint through a database link.

Action:
Login directly then create constraint.

BRW-15377
Create or remove constraint is only for table

Category:
Other

Cause:
User tried to create or remove a constraint on non-table database object.

Action:
This action is not supported.

BRW-15378
Table already removed. Create/remove on constraint ignored

Category:
Other

Cause:
User tried to create or remove a constraint on an already removed table.

Action:
Revert table before further modifying it.

BRW-15379
Primary or unique already exists

Category:
Other

Cause:
Duplicate primary or unique key.

Action:
No action required.

BRW-15380
Foreign key must reference primary or unique key

Category:
Other

Cause:
The specified foreign key does not reference a primary or unique key.

Action:
Make sure the foreign key references a primary or unique key.

BRW-15381
Number of columns mismatch between foreign and primary/unique key

Category:
Other

Cause:
The foreign key does not match the number of columns in the primary or unique key.

Action:
Make sure the number of columns are the same.

BRW-15382
Foreign key already exists

Category:
Other

Cause:
Foreign key already exists.

Action:
No action required.

BRW-15383
A table can only have one primary key

Category:
Other

Cause:
User tried to specify more than one primary key per table.

Action:
Remove the old primary key and recreate it.

BRW-15384
Cannot remove or modify a keys referenced by foreign keys

Category:
Other

Cause:
Primary or unique key is referenced by foreign keys.

Action:
Remove foreign keys first then remove primary/unique keys.

BRW-15385
Cannot duplicate view from PUBLIC database link as a view

Category:
Other

Cause:
Unable to read SQL statement (LONG column) from PUBLIC database link.

Action:
This action is not supported.

BRW-15386
Circular reference detected in synonym {1}

Category:
Other

Cause:
The synonym has a circular reference in the data dictionary.

Action:
Do not include the particular synonym.

BRW-15387
Login failed

Category:
Other

Cause:
Database or SQLNet error occurred.

Action:
Check the login information and try again.

BRW-15388
Unable to load database relationships

Category:
Other

Cause:
Schema internal error in loading database relationships.

Action:
Contact support if this is not expected.

BRW-15389
Unable to load list of accessible owners

Category:
Other

Cause:
Schema internal error in loading list of accessible owners.

Action:
Contact support if this is not expected.

BRW-15390
Unable to load list of accessible tables

Category:
Other

Cause:
Schema internal error in loading list of data tables.

Action:
Contact support if this is not expected.

BRW-15391
Unable to load table

Category:
Other

Cause:
Schema internal error in loading data table.

Action:
Contact support if this is not expected.

BRW-15392
Unable to load table

Category:
Other

Cause:
Schema internal error in loading table.

Action:
Contact support if this is not expected.

BRW-15393
Unable to load synonym

Category:
Other

Cause:
Schema internal error in loading synonym.

Action:
Contact support if this is not expected.

BRW-15394
Unable to load query

Category:
Other

Cause:
Schema internal error in loading query.

Action:
Contact support if this is not expected.

BRW-15395
Unable to load table column information

Category:
Other

Cause:
Schema internal error in loading column information.

Action:
Contact support if this is not expected.

BRW-15396
Unable to load synonym column information

Category:
Other

Cause:
Schema internal error in loading synonym column information.

Action:
Contact support if this is not expected.

BRW-15397
Unable to load constraints

Category:
Other

Cause:
Schema internal error in loading constraints.

Action:
Contact support if this is not expected.

BRW-15398
Unable to find primary key information

Category:
Other

Cause:
Schema internal error in finding primary keys.

Action:
Contact support if this is not expected.

BRW-15399
Unable to find foreign key information

Category:
Other

Cause:
Schema internal error in finding foreign keys.

Action:
Contact support if this is not expected.

BRW-15400
Unable to load table and column comments

Category:
Other

Cause:
Schema internal error in getting comments.

Action:
Contact support if this is not expected.

BRW-15401
Error in loading database link {1}

Category:
Other

Cause:
Schema internal error in loading database link.

Action:
Refer to accompanying error messages for more information.

BRW-15402
Error in loading owner {1}

Category:
Other

Cause:
Schema internal error in loading database link.

Action:
Refer to accompanying error messages for more information.

BRW-15403
Error in loading table {1}

Category:
Other

Cause:
Schema internal error in loading data table.

Action:
Refer to accompanying error messages for more information.

BRW-15404
Error in loading primary key constraint for {1} ({2})

Category:
Other

Cause:
Schema internal error in loading primary constraint.

Action:
Refer to accompanying error messages for more information.

BRW-15405
Error in loading foreign key constraint {1}

Category:
Other

Cause:
Schema internal error in loading foreign constraint.

Action:
Refer to accompanying error messages for more information.

BRW-15406
Error in loading synonym {1}

Category:
Other

Cause:
Schema internal error in loading primary constraint.

Action:
Refer to accompanying error messages for more information.

BRW-15407
Table referred to by synonym {1} no longer exists

Category:
Other

Cause:
User tried to create a synonym for a nonexistent data table.

Action:
Recreate the synonym.

BRW-15408
Error in loading column information for {1}

Category:
Other

Cause:
Oracle error or the data table has been removed.

Action:
Recreate the data table.

BRW-15409
Error in loading constraint information for {1} ({2})

Category:
Other

Cause:
Oracle error.

Action:
Try it again.

BRW-15410
Table that foreign key {1} ({2}) refers to is inaccessible

Category:
Other

Cause:
The table that the foreign key refers to is inaccessible.

Action:
Grant the table to the current user.

BRW-15411
Logout failed

Category:
Other

Cause:
Internal error in logging out.

Action:
Exit or close the document.

BRW-15412
Table of query {1} was modified. Query loaded as view.

Category:
Other

Cause:
The view that the query depends on has been modified after the last save.

Action:
Open the query and save it again to use it as a data table.

BRW-15413
Table of query {1} was removed. Query will not be loaded.

Category:
Other

Cause:
The view that the query depends on has been removed.

Action:
Open the query, and save it again to use it as a data table.

BRW-15414
Table {1} no longer exists

Category:
Other

Cause:
This data table no longer exists in the database.

Action:
Contact system administrator if you need this table.

BRW-15415
Maximum number (254) of table columns exceeded

Category:
Other

Cause:
User tried to load a data table that has more than 254 columns.

Action:
Contact system administrator.

BRW-15416
Maximum number (8192) of tables per user exceeded

Category:
Other

Cause:
User owns too many data tables.

Action:
Contact system administrator.

BRW-15417
Maximum number (1024) of owners and databases exceeded

Category:
Other

Cause:
User tried to load too many user, owner, and database links.

Action:
Contact system administrator.

BRW-15418
Unable to find database link information

Category:
Other

Cause:
This database does not support database link, or database error.

Action:
Try again later if this is unexpected.

BRW-15419
Unable to find synonym information

Category:
Other

Cause:
This database does not support synonyms, or database error.

Action:
Try again later if this is unexpected.

BRW-15420
Unable to find constraint information

Category:
Other

Cause:
This database does not support constraints, or database error.

Action:
Try again later if this is unexpected.

BRW-15421
Unable to find table comment table

Category:
Other

Cause:
This database does not support comments on table, or database error.

Action:
Try again later if this is unexpected.

BRW-15422
Unable to find table Column comments table

Category:
Other

Cause:
This database does not support comments on column, or database error.

Action:
Try again later if this is unexpected.

BRW-15423
Synonym to SEQUENCE is not currently supported

Category:
Other

Cause:
User tried to load a synonym that refers to a sequence.

Action:
This action is not supported.

BRW-15424
Maximum number of login attempts (3) exceeded

Category:
Other

Cause:
User tried to login too many times.

Action:
Contact system administrator for correct username, password, and connect strings.

BRW-15425
End User Layer dictionary not installed

Category:
Other

Cause:
The End User Layer meta-data dictionary was not found.

Action:
Install the End User Layer dictionary or run with DICTIONARY=NATIVE option.

BRW-15430
Index information not loaded

Category:
Other

Cause:
Cannot find index table.

Action:
This is a non-Oracle database; try an ODBC driver.

BRW-15433
Create snapshot with only {1} maximum columns.

Category:
Other

Cause:
User tried to create more than the maximum number of allowed columns in a snapshot.

Action:
Create fewer columns.

BRW-15434
Maximum columns in table is {1}

Category:
Other

Cause:
User tried to create more than the maximum number of allowed columns in a table.

Action:
Create fewer columns.

BRW-15435
DBA privilege is needed to perform this operation

Category:
Other

Cause:
Need DBA privileges.

Action:
Ask your system administrator to grant you DBA privilege.

BRW-15437
Index already exists

Category:
Other

Cause:
User tried to create an index that is the same as an already existing index.

Action:
No action required.

BRW-15438
Index must be on columns from the same table

Category:
Other

Cause:
user tried to create an index on columns from different tables.

Action:
Create the index on columns from the same table.

BRW-15439
Cannot create new tables through database links

Category:
Other

Cause:
User tried to create data tables through database links.

Action:
This operation is not allowed. Login directly then create.

BRW-15440
New columns cannot be created through database links

Category:
Other

Cause:
User tried to create columns through database links.

Action:
This operation is not allowed. Login directly and create.

BRW-15441
User has no CREATE INDEX privilege

Category:
Other

Cause:
User tried to create an index on data table without proper privileges

Action:
Obtain CREATE INDEX privilege on this data table.

BRW-15444
Adding columns is only supported for tables

Category:
Other

Cause:
User tried to add columns to a view, snapshot, synonym, or query.

Action:
This operation is not allowed.

BRW-15445
Cannot remove columns of synonyms, duplicated views or snapshots

Category:
Other

Cause:
User tried to remove columns from a view, snapshot, synonym, or query.

Action:
This operation is not allowed.

BRW-15446
Unable to copy constraints for {1}

Category:
Other

Cause:
Error duplicating constraints.

Action:
No action required.

BRW-15447
Cannot remove Query. Use File Delete... from Query window

Category:
Other

Cause:
User tried to remove a query.

Action:
This is not legal from the Schema Builder. Use the Query window instead.

BRW-15448
Cannot copy Query. Use File Save As... from Query window

Category:
Other

Cause:
User tried to copy a query.

Action:
This is not legal from the Schema Builder. Use the Query window instead.

BRW-15449
Cannot copy with data from table with only LONG columns

Category:
Data

Cause:
User tried to copy a table with a LONG column.

Action:
Database does not support this.

BRW-15450
Operation not allowed on removed table

Category:
Other

Cause:
User tried to do something to a removed data table.

Action:
Undo the remove first.

BRW-15451
Operation not allowed on removed column

Category:
Other

Cause:
User tried to do something to a removed column.

Action:
Undo the remove first.

BRW-15452
Cannot rename another owner's table

Category:
Other

Cause:
User tried to set the name of a granted data table.

Action:
This is not allowed. Ask the owner to do it for you.

BRW-15453
Cannot rename table at database link

Category:
Other

Cause:
User tried to set the name on a data table at a database link.

Action:
Ask the owner to do this for you.

BRW-15454
Renaming columns is only supported on table and view columns

Category:
Other

Cause:
User tried to set column name for a snapshot, synonym, or query.

Action:
This is not allowed.

BRW-15455
Setting column type is only supported on table columns

Category:
Other

Cause:
User tried to set column type for a view, snapshot, synonym, or query.

Action:
This is not allowed.

BRW-15456
Cannot change column type of an existing column

Category:
Other

Cause:
User tried to change column type of an existing column.

Action:
This is not allowed.

BRW-15457
Default values are allowed only on table columns

Category:
Other

Cause:
User tried to set default for a synonym, snapshot, view, or query.

Action:
This is not allowed.

BRW-15458
Setting length is supported only on table columns

Category:
Other

Cause:
User tried to set length for a synonym, snapshot, view, or query.

Action:
This is not allowed.

BRW-15459
Cannot set length for DATE, LONG, or ROWID datatypes

Category:
Other

Cause:
User tried to set the length for DATE, LONG, or ROWID datatypes.

Action:
This is not allowed.

BRW-15460
Setting scale is allowed only on table columns

Category:
Other

Cause:
User tried to set scale for synonym, snapshot, view, or query columns.

Action:
This is not allowed.

BRW-15461
Cannot set scale for DATE, LONG, or ROWID datatypes

Category:
Other

Cause:
User tried to set scale for DATE, LONG, or ROWID columns.

Action:
This is not allowed.

BRW-15462
Setting precision is allowed only on table columns

Category:
Other

Cause:
User tried to set precision for synonym, snapshot, view, or query columns.

Action:
This is not allowed.

BRW-15463
Setting precision is allowed only on NUMBER datatype

Category:
Other

Cause:
User tried to set precision on columns other than NUMBER.

Action:
This is not allowed.

BRW-15464
Altering column position is allowed only on table columns

Category:
Other

Cause:
User tried to set column position on non-table database objects.

Action:
This is not allowed.

BRW-15465
Cannot change the position of existing column.

Category:
Other

Cause:
User tried to change column position of existing table.

Action:
This is not allowed.

BRW-15466
Table name too long (Max {1} bytes)

Category:
Other

Cause:
Data Table name to long.

Action:
Shorten the name and try again.

BRW-15467
Name already in use. Please choose another name.

Category:
Other

Cause:
Name already in use.

Action:
Choose another name.

BRW-15468
Column name too long (Max {1} bytes)

Category:
Other

Cause:
Column name too long.

Action:
Shorten the name and try again.

BRW-15469
Length of NUMBER column must be between {1} and {2}

Category:
Other

Cause:
Illegal range for length of NUMBER column.

Action:
Specify a legal length parameter.

BRW-15470
Length of CHAR or RAW column must be between {1} and {2}

Category:
Other

Cause:
Illegal range for length of CHAR column.

Action:
Specify a legal length parameter.

BRW-15471
Precision must be between {1} and {2}

Category:
Other

Cause:
Illegal range for precision.

Action:
Specify a legal length parameter.

BRW-15472
Cannot decrease length of existing column

Category:
Other

Cause:
User tried to decrease the length of an existing column.

Action:
This is not allowed.

BRW-15473
Cannot decrease scale of existing column

Category:
Other

Cause:
User tried to decrease scale of an existing column.

Action:
This is not allowed.

BRW-15474
Cannot decrease precision of existing column

Category:
Other

Cause:
User tried to decrease precision of an existing column.

Action:
This is not allowed.

BRW-15475
Table can have at most one LONG column

Category:
Other

Cause:
User tried to create more than one LONG or RAW column per table.

Action:
This is not allowed.

BRW-15476
Error in loading index for {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15477
Error in creating table {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15478
Error in creating view {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15479
Error in creating synonym {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15480
Error in creating index {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15481
Error in dropping {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15482
Error in dropping table {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15483
Error in dropping view {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15484
Error in dropping synonym {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15485
Error in dropping index {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15486
Error in renaming {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15487
Error in setting comment for table {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15488
Error in setting comment for column {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15489
Error in loading index {1} for {2}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15490
Error in loading table privilege for {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15491
Error in loading column privilege for {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15492
Error in altering table {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15493
Operation currently not supported

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15494
Error in loading SQL text of views

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15495
Error in loading SQL text for view {1}

Category:
Other

Cause:
Internal error.

Action:
Contact support.

BRW-15496
Scale must be between {1} and {2}

Category:
Other

Cause:
Illegal value for scale.

Action:
Input legal value for scale.

BRW-15497
Index can only be created on TABLE columns

Category:
Other

Cause:
User tried to create index on a database object other than a TABLE.

Action:
Create index on TABLE columns only.

BRW-15498
Cannot modify a query

Category:
Other

Cause:
It is not legal to modify a query.

Action:
Open the query and modify it as a Browser document.

BRW-15499
Cannot set column attributes of table duplicated with data

Category:
Data

Cause:
User tried to set the column type of a table duplicated with data.

Action:
First commit the table then try again.

BRW-15500
{1}

Category:
Other

Cause:
Oracle error

Action:
None.

BRW-15501
No more application virtual memory

Category:
Memory

Cause:
No more disk space or system memory for Virtual Memory Manager.

Action:
Close a document or make some room on your disk.

BRW-15502
Can only have {1} rows per document

Category:
Other

Cause:
Exceeded self-imposed, compile-time row maximum.

Action:
Consider adding conditions to the query.

BRW-15504
Unable to determine database character set

Category:
Other

Cause:
There was a problem with SELECT USERENV('LANGUAGE') FROM DUAL.

Action:
Non-Oracle database--not supported.

BRW-15505
Unable to open virtual memory file

Category:
Memory

Cause:
No write permission or file system full.

Action:
Change permission on directory or delete some files.

BRW-15506
Unable to close virtual memory file

Category:
Memory

Cause:
Operating system error.

Action:
Ask system administrator for assistance.

BRW-15507
Unable to read from virtual memory file

Category:
Memory

Cause:
Virtual memory file does not exist.

Action:
Make sure the virtual memory file is opened.

BRW-15508
Unable to write to virtual memory file

Category:
Memory

Cause:
File system is full, or virtual memory file was not opened.

Action:
Delete some files. Make sure virtual memory file is opened.

BRW-15509
Unable to create virtual memory manager

Category:
Memory

Cause:
Internal error, or out of memory.

Action:
Ask system administrator for assistance.

BRW-15511
Maximum virtual memory size exceeded

Category:
Memory

Cause:
User input is too big for virtual memory size.

Action:
Try again.

BRW-15513
Null value in command '{1}'

Category:
Other

Cause:
User entered <command>= on the command line with no option selected.

Action:
Add a value for <command>.

BRW-15514
Null command in command line

Category:
Other

Cause:
User entered =<value> at command line but did not specify a command.

Action:
Add the command.

BRW-15515
Unrecognized command '{1}' in command line

Category:
Other

Cause:
User entered an illegal command at command line.

Action:
Change command.

BRW-15516
Command '{1}' specified twice in command line

Category:
Other

Cause:
User entered a command twice at command line.

Action:
Remove one.

BRW-15517
Incompatible commands '{1}' and '{2}' specified

Category:
Other

Cause:
User entered 2 incompatible commands at command line.

Action:
Remove one.

BRW-15518
Invalid option '{1}' in command '{2}'

Category:
Other

Cause:
User entered an illegal option to a command at command line.

Action:
Change option.

BRW-15519
Multiple login specifications in command line

Category:
Other

Cause:
User entered 2 login specifications at command line.

Action:
Remove one.

BRW-15520
Invalid document name '{1}' in command line

Category:
Other

Cause:
User entered an illegal document name at command line.

Action:
Change document name.

BRW-15521
'{1}' command specified without a document

Category:
Other

Cause:
User entered a command without specifying a document at command line.

Action:
Add missing document.

BRW-15522
'{1}' command specified without '{2}'

Category:
Other

Cause:
User entered a command without another required command.

Action:
Add missing command.

BRW-15523
Mismatched parentheses in '{1}' command

Category:
Other

Cause:
User entered mismatched parentheses in the command line.

Action:
Correct mismatched parentheses.

BRW-15530
Cannot edit a deleted row

Category:
Other

Cause:
User tried to edit a row which is marked for deletion.

Action:
Undelete the row first.

BRW-15531
Row has been deleted from the database

Category:
Other

Cause:
Another user deleted this row since you last ran the query.

Action:
Contact support. This should never happen.

BRW-15532
Row has been modified by another user. Requery.

Category:
Other

Cause:
Another user updated this row since you last ran the query.

Action:
Try again.

BRW-15533
Row is currently locked by another user.

Category:
Other

Cause:
Someone else is editing this row.

Action:
Try again later.

BRW-15539
Error in inserting {1} row(s)

Category:
Other

Cause:
One or more rows in input file failed on insert.

Action:
Modify input file or ignore.

BRW-15540
Operation not allowed on data of this type

Category:
Data

Cause:
User tried to edit a cell with data of an uneditable type.

Action:
Unknown.

BRW-15541
Too many edited rows. Please select Commit

Category:
Other

Cause:
Too many pending INSERTS, UPDATES or DELETES in a document.

Action:
Select Commit or Revert.

BRW-15545
Error in reading QXF file. Parsing halted.

Category:
Other

Cause:
Syntax error in reading QXF file.

Action:
Fix QXF file.

BRW-15546
Parse Error: Line {1}

Category:
Other

Cause:
Syntax at that particular line.

Action:
Debug that line.

BRW-15547
Operator unspecified in relationship block.

Category:
Other

Cause:
Operator unspecified in relationship block in QXF File.

Action:
Specify an operator field within the block.

BRW-15548
Error: Argument missing in {1} of relationship block.

Category:
Other

Cause:
No argument in a column field in a relationship block. No argument in the CONDITION_TEXT field within condition block.

Action:
Specify the column name in that field. Specify the CONDITION_TEXT field.

BRW-15550
Illegal INCLUSION_ORDER value ({1}) in expression {2}.

Category:
Other

Cause:
Illegal INCLUSION_ORDER value in expression.

Action:
Correct INCLUSION_ORDER value.

BRW-15551
Expression {1} included but INCLUSION_ORDER unspecified.

Category:
Other

Cause:
The INCLUSION_ORDER unspecified for an included expression block.

Action:
Specify the INCLUSION_ORDER field.

BRW-15552
Expression {1} not included but INCLUSION_ORDER is non-null

Category:
Other

Cause:
Expression is not included (INCLUDED = FALSE) but INCLUSION_ORDER is non-null.

Action:
Correct the values in these fields.

BRW-15553
Error: Empty TEXT string in expression {1}.

Category:
Other

Cause:
The TEXT string is unspecified within a QXF expression block.

Action:
Specify the TEXT string.

BRW-15554
Error: SORT_PRIORITY unspecified for sorted expression {1}.

Category:
Other

Cause:
SORT_PRIORITY unspecified for sorted expression.

Action:
Specify the SORT_PRIORITY.

BRW-15555
Illegal INCLUSION_ORDER value for field {1}in table {2}.

Category:
Other

Cause:
Illegal INCLUSION_ORDER value for field.

Action:
Correct the INCLUSION_ORDER value.

BRW-15556
Field {1} in table {2} included but INCLUSION_ORDER is null.

Category:
Other

Cause:
Field is included (INCLUDED = FALSE) but INCLUSION_ORDER is unspecified.

Action:
Correct the values in these fields.

BRW-15557
Field {1} (table {2}) excluded but INCLUSION_ORDER exists.

Category:
Other

Cause:
The field in specified data table is not included but the INCLUSION_ORDER is non-null.

Action:
Correct the values in these fields.

BRW-15558
SORT_PRIORITY unspecified for sorted field {1} in table {2}.

Category:
Other

Cause:
SORT_PRIORITY unspecified for a sorted field.

Action:
Specify the SORT_PRIORITY for that field.

BRW-15559
Error: Illegal value ({1}) for INCLUSION_ORDER in table {2}.

Category:
Other

Cause:
A negative value in inclusion order.

Action:
Correct that value.

BRW-15560
Table {1} included but INCLUSION_ORDER unspecified.

Category:
Other

Cause:
Data Table included (INCLUDED = TRUE) but INCLUSION_ORDER is unspecified.

Action:
Correct the values in these fields.

BRW-15561
Table {1} is excluded but INCLUSION_ORDER is non-null.

Category:
Other

Cause:
Data Table not included (INCLUDED = FALSE) but INCLUSION_ORDER is non-null.

Action:
Correct the values in these fields.

BRW-15562
Error: There should be no more than one main condition block.

Category:
Other

Cause:
There are more than one main (root) condition blocks.

Action:
Eliminate some condition blocks, or use a conjunction.

BRW-15563
Error: QXF file version 1.0 expected.

Category:
Other

Cause:
Illegal version number specified in VERSION field.

Action:
Modify the version.

BRW-15564
Parse Error: Line {1}: Invalid font style {2}.

Category:
Other

Cause:
Invalid font style.

Action:
Check font style and correct it.

BRW-15565
Parse Error: Line {1}: Invalid font style argument.

Category:
Other

Cause:
Invalid font style argument.

Action:
Check font style strings and correct them.

BRW-15566
Parse Error: Line {1}: Invalid aggregate function {2}

Category:
Other

Cause:
Invalid aggregate function name.

Action:
Correct the function name.

BRW-15567
Parse Error: Line {1}: Invalid summarize argument.

Category:
Other

Cause:
Invalid summarize field argument.

Action:
Correct the field argument.

BRW-15568
Parse Error: Line {1}: Invalid field argument.

Category:
Other

Cause:
Invalid field argument.

Action:
Correct field argument.

BRW-15569
Warning: QXF file is only partially loaded because of error.

Category:
Other

Cause:
Error in loading QXF file.

Action:
Correct those errors.

BRW-15570
Parse Error: Line {1}: Invalid operator {2} in relationship block.

Category:
Other

Cause:
Invalid Operator within relationship block.

Action:
Check operator and correct it.

BRW-15571
Parse Error: Line {1}: Invalid operator field argument.

Category:
Other

Cause:
Invalid Object ID within Derived Item Expression.

Action:
Correct Object ID in dictionary.

BRW-15572
Inconsistent object IDs in derived item expression.

Category:
Other

Cause:
Invalid operator field argument within relationship block.

Action:
Check operator strings and correct them.

BRW-15580
Unable to load list of accessible business areas

Category:
Other

Cause:
End User Layer is missing business area tables.

Action:
Reinstall End User Layer. Ask system administrator for assistance.

BRW-15581
Cannot add columns to table created with duplicate data

Category:
Data

Cause:
User tried to add columns to a table created with duplicate table data.

Action:
Commit the duplicated table then try again.

BRW-15582
New or duplicate table is only allowed on existing table.

Category:
Other

Cause:
Create new table on another new/duplicate/modified table.

Action:
Commit the new/duplicate/modified table first.

BRW-15583
Index requires at least one column

Category:
Other

Cause:
User tried to remove the last column of an index.

Action:
Add other columns then remove.

BRW-15584
Column {1} is of type LONG and will not be copied

Category:
Other

Cause:
Cannot copy a LONG column when creating a snapshot.

Action:
Column cannot be copied.

BRW-15600
Syntax not supported

Category:
Other

Cause:
Attempted to parse unsupported syntax

Action:
Use alternate Oracle 8 syntax.

BRW-15601
Invalid Oracle 8 SQL syntax

Category:
Other

Cause:
Cannot use Oracle 8 language syntax

Action:
Use Oracle 7 SQL.

BRW-15602
Type Constructor in Oracle 8 SQL is not supported

Category:
Other

Cause:
Oracle 8 SQL's type contructors are not supported.

Action:
Revert to Oracle 7.

BRW-15603
REF in Oracle 8 SQL is not supported

Category:
Other

Cause:
Oracle 8 SQL's REF is not supported.

Action:
Use Oracle 7 instead.

BRW-15604
CAST in Oracle 8 SQL is not supported

Category:
Other

Cause:
Oracle 8 SQL's CAST is not supported.

Action:
Use Oracle 7 instead.

BRW-15605
MULTISET in Oracle 8 SQL is not supported

Category:
Other

Cause:
Oracle 8 SQL's MULTISET is not supported.

Action:
Use Oracle 7 intsead.

BRW-15606
METHODS in Oracle 8 SQL is not supported

Category:
Other

Cause:
Oracle 8 SQL's METHODS is not supported.

Action:
Use Oracle 7 instead.

BRW-15607
THE subquery in Oracle 8 SQL is not supported

Category:
Other

Cause:
Oracle 8 SQL's THE subquery is not supported.

Action:
Use Oracle 7 instead.

BRW-15608
PARTITION of tables in Oracle 8 SQL is not supported

Category:
Other

Cause:
Oracle 8 SQL's PARTITION of tables is not supported.

Action:
Use Oracle 7 instead.

BRW-15609
The TABLE keyword in a subquery in Oracle 8 SQL is not supported

Category:
Other

Cause:
TABLE in subquery is not supported.

Action:
Use Oracle 7 instead.

BRW-15610
Rename the Table as a Table Alias

Category:
Other

Cause:
Attempt to use a table instead of a table alias

Action:
Rename the table with a table alias.

BRW-15641
Help system initialization failed. Help will be unavailable.

Category:
Other

Cause:
Unable to locate help document or help resource file.

Action:
User may continue but help menu is unavailable. Use online or paper documentation.

BRW-15643
Resource file not found ({1}), trying default resource file.

Category:
Other

Cause:
NLS_LANG set but file not found.

Action:
Try to open the resource file using the default language.

BRW-15644
Unable to locate help document ({1}), trying default help document.

Category:
Other

Cause:
NLS_LANG set but file not found.

Action:
Try to open the help doc using the default language.

BRW-15647
Unable to locate help document

Category:
Other

Cause:
Could not find help file in correct directory with correct language.

Action:
Check Browser directory structure. Make sure NLS_LANG is set correctly.

BRW-15648
Help system creation error

Category:
Other

Cause:
Help system could not start up.

Action:
Browser could not find the help resource file, or NLS_LANG is not set, or memory is low.

BRW-15649
Input for {1} was too low. Minimum valid number is {2}.

Category:
Other

Cause:
The value input was too low.

Action:
Try again with a higher value.

BRW-15650
Input for {1} was too high. Maximum valid number is {2}.

Category:
Other

Cause:
The value input was too high.

Action:
Try again with a lower value.

BRW-15651
Input for {1} was out of range. Must be between {2} and {3}.

Category:
Other

Cause:
The value input was out of the valid range.

Action:
Try again with a valid number.

BRW-15652
Value was reset to {1}.

Category:
Other

Cause:
The value input was changed because it was out of the valid range.

Action:
Try again with a valid number or Browser will use the value shown.

BRW-15653
Pref file error: Value {1} was too low. Minimum valid number is {2}.

Category:
Other

Cause:
The value input was too low.

Action:
Try again with a higher value.

BRW-15654
Pref file error: Value {1} was too high. Maximum valid number is {2}.

Category:
Other

Cause:
The value input was too high.

Action:
Try again with a lower value.

BRW-15655
Pref file error: Value {1} out of range. Must be between {2} and {3}.

Category:
Other

Cause:
The value input was out of the valid range.

Action:
Try again with a valid number.

BRW-15656
Pref file error: Value for {1} not recognized

Category:
Other

Cause:
The value set in the preference file was invalid.

Action:
Try again with a valid number.

BRW-15657
Value for OWNERLIST=NAME must contain at least one name

Category:
Other

Cause:
The value for OWNERLIST=NAME was NULL.

Action:
Try again with a valid name

BRW-15900
Unable to find time period information

Category:
Other

Cause:
This database does not support time periods, or database error.

Action:
Try again later if this is unexpected.

BRW-15901
Data source {1} referred to by object {2} no longer exists

Category:
Data

Cause:
Base data source of object has been removed.

Action:
Refresh/delete object.

BRW-15902
Table referred to by object {1} no longer exists

Category:
Other

Cause:
Base data source of object has been removed.

Action:
Refresh/delete object.

BRW-15903
Opposite table {1} is not in a business area. Join info inaccessible.

Category:
Other

Cause:
Relationship: Opposite data table/object not in any group.

Action:
Grant that object to a group.

BRW-15904
Relationship name cannot be longer than {1} bytes

Category:
Other

Cause:
Relationship Name longer than limit.

Action:
Use a shorter name.

BRW-15905
Column heading cannot be longer than {1} bytes

Category:
Other

Cause:
Item Heading longer than limit.

Action:
Use a shorter heading.

BRW-15906
Column format cannot be longer than {1} bytes

Category:
Other

Cause:
Item Format longer than limit.

Action:
Use a shorter format.

BRW-15907
Column display width cannot have more than {1} digits

Category:
Other

Cause:
Item Display Width Precision longer than limit.

Action:
Use Shorter Display width.

BRW-15908
Time period name cannot be longer than {1} bytes

Category:
Other

Cause:
Time Period Name too long.

Action:
Use a shorter time period name.

BRW-15909
Period column and sequence column of time period are the same

Category:
Other

Cause:
Period and sequence columns of time period set to the same column.

Action:
make sure period and sequence columns are different.

BRW-15910
Unable to load time period {1}

Category:
Other

Cause:
Schema internal error in loading time period.

Action:
Refer to accompanying error messages for more information.

BRW-15911
Time period {1} already exists

Category:
Other

Cause:
Time period name must be unique.

Action:
Create time period under a different name.

BRW-15912
Illegal display width value.

Category:
Other

Cause:
Illegal display width value.

Action:
Re-enter a legal value.

BRW-15913
{1} key text cannot be empty.

Category:
Other

Cause:
Foreign or Primary Key text is empty.

Action:
Enter text for primary or foreign key.

BRW-15914
Relationship name cannot be empty.

Category:
Other

Cause:
Relationship name is null.

Action:
Enter relationship name.

BRW-15924
Business area name cannot be empty

Category:
Other

Cause:
Business area name is empty or contains only spaces.

Action:
Enter a new name.

BRW-15925
Table {1} has already been imported as {2}

Category:
Other

Cause:
Table can only be imported once with a given name.

Action:
Import table under a different name.

BRW-15926
Business area {1} already exists

Category:
Other

Cause:
Business area name must be unique.

Action:
Create business area under a different name.

BRW-15927
Business area {1} already contains a table named {2}

Category:
Other

Cause:
Table name must be unique within a business area.

Action:
Rename/reimport table and add to business area.

BRW-15928
Business area name too long (Max {1} bytes)

Category:
Other

Cause:
Business area name too long.

Action:
Shorten the name and try again.

BRW-15929
Business area description too long (Max {1} bytes)

Category:
Other

Cause:
Business area description too long.

Action:
Shorten the description and try again.

BRW-15930
Error committing table {1}

Category:
Other

Cause:
Error occurred while committing table.

Action:
Try again.

BRW-15931
Error committing business area {1}

Category:
Other

Cause:
Error occurred while committing business area.

Action:
Try again.

BRW-15932
Error committing time period {1}

Category:
Other

Cause:
Error occurred while committing time period.

Action:
Try again.

BRW-15933
Error committing relationship {1}

Category:
Other

Cause:
Error occurred while committing relationship

Action:
Try again.

BRW-15937
Error generating SQL for table {1}

Category:
Other

Cause:
Error occurred while generating SQL for a table.

Action:
Try again.

BRW-15938
Error generating SQL for business area {1}

Category:
Other

Cause:
Error occurred while generating SQL for a business area.

Action:
Try again.

BRW-15939
Error generating SQL for time period {1}

Category:
Other

Cause:
Error occurred while generating SQL for a time period.

Action:
Try again.

BRW-15940
Error generating SQL for relationship {1}

Category:
Other

Cause:
Error occurred while generating SQL for relationship.

Action:
Try again.

BRW-15950
No Query Builder tables--Database open/save is disabled

Category:
Other

Cause:
There is no Query Builder system query table in the database.

Action:
Create a system query table (run the Query Builder install script).

BRW-15951
Product user profile information not loaded

Category:
Other

Cause:
Cannot load the user profile table.

Action:
Ask system administrator to create one.

BRW-15952
User privilege table not loaded

Category:
Other

Cause:
Missing USER_USERS table (Non Oracle or oracle V7 database).

Action:
None available.

BRW-15953
Table privilege table not loaded

Category:
Other

Cause:
Cannot find Privilege table.

Action:
Non-Oracle database or Oracle V7 database.

BRW-15954
Oracle Query Builder 2.5 tables are missing or not installed properly

Category:
Other

Cause:
No BROWSER_DOCS_SQL table.

Action:
Re-install Query Builder 2.5 tables.

BRW-15955
Query returned zero rows

Category:
Other

Cause:
Query returned no rows.

Action:
Modify the query so that it requests data that exists in the database.

BRW-16000
Document saved using End User Layer, not Native dictionary. Continue?

Category:
Other

Cause:
User tried to open in Native mode a document saved using the End User Layer.

Action:
Run with DICTIONARY=ENDUSER or End User Layer objects will be inaccessible.

BRW-16001
Document saved using Native dictionary, not End User Layer. Continue?

Category:
Other

Cause:
User tried to open in ENDUSER mode a document saved using the Native dictionary.

Action:
Run with DICTIONARY=NATIVE or some database objects may be inaccessible.

BRW-16250
Document already exists. Do you want to overwrite?

Category:
Other

Cause:
User tried to Save As over an existing document.

Action:
User may overwrite or cancel.

BRW-16251
Table has been modified. Continue?

Category:
Other

Cause:
View was removed and recreated; may be inconsistent with document.

Action:
Either continue or abort save.

BRW-16500
Memory not available for local sort. Re-execute?

Category:
Memory

Cause:
All rows not yet fetched for local sort.

Action:
Re-execute query now or later.

BRW-16503
Data not available for local sort. Re-execute?

Category:
Data

Cause:
All rows not yet fetched for local sort.

Action:
Re-execute query now or later.

BRW-16504
Data not available for local break. Re-execute?

Category:
Data

Cause:
All rows not yet fetched for local break.

Action:
Re-execute query now or later.

BRW-16525
Query may require a Cartesian product. Continue?

Category:
Other

Cause:
Query combines results of unrelated tables.

Action:
Ignore message or relate tables before executing. Refer to help or documentation for details.

BRW-16531
Redefine parameter {1}?

Category:
Other

Cause:
User entered previously deleted parameter in expression or condition.

Action:
Press OK if this is what you intended.

BRW-16532
Parameter {1} does not exist. Define?

Category:
Other

Cause:
User entered new parameter in expression or condition.

Action:
Press OK if this is what you intended.

BRW-16549
Revert will undo all changes on these tables. Revert anyway?

Category:
Other

Cause:
Confirmation before reverting data tables.

Action:
Select OK to revert all selected data tables, Cancel to cancel the operation.

BRW-16550
Table %s has primary/unique keys that are referenced. Remove?

Category:
Other

Cause:
Table contains constraints.

Action:
Select OK to remove the data table, Cancel to cancel the operation.

BRW-16551
Column has primary/unique keys or indexes. Remove anyway?

Category:
Other

Cause:
Column is used by constraints or indexes.

Action:
Select OK to remove the column, Cancel to cancel the operation.

BRW-16552
Disable all constraints?

Category:
Other

Cause:
Message to confirm that all constraints should be disabled.

Action:
User may confirm or cancel.

BRW-16553
Enable all constraints?

Category:
Other

Cause:
Message to confirm that all constraints should be enabled.

Action:
User may confirm or cancel.

BRW-16575
There are uncommitted edits which will be lost. Commit?

Category:
Other

Cause:
User has tried to exit the Data Editor without committing changes.

Action:
Select Commit or lose changes.

BRW-16576
Defined Column, Summary or Break values may not be current. Re-execute?

Category:
Other

Cause:
Values edited while displaying breaks, summaries, or defined columns.

Action:
Execute query to update values.

BRW-16620
Save changes to query document '%s'?

Category:
Other

Cause:
Message to prompt user to save changes when closing/quitting.

Action:
User may save or abort changes, or cancel.

BRW-16621
Revert to previously saved version of document '%s'?

Category:
Other

Cause:
Message to prompt user to revert to older document version.

Action:
User may continue or cancel operation.

BRW-16622
File %s already exists. Do you want to overwrite?

Category:
Other

Cause:
Message for overwrite alert in export data.

Action:
User may overwrite file or cancel.

BRW-16623
There is no data available for this operation.

Category:
Data

Cause:
Alert message if number of rows or columns available to print is zero.

Action:
User should try re-executing the query, or include some columns.

BRW-16624
Query definition has changed. Data may not be current. Continue?

Category:
Data

Cause:
Query document has changed since last execute.

Action:
Either re-execute the query, continue export, or cancel.

BRW-16625
The printer does not support all fonts needed. Substitute fonts?

Category:
Other

Cause:
The font or some style or weight does not exist for the selected printer.

Action:
User may continue with font substitution or cancel.

BRW-16626
Not enough memory for Print Preview.

Category:
Memory

Cause:
Unable to create bitmap for print preview.

Action:
No action required.

BRW-16627
There is no data available for this operation. Execute query?

Category:
Data

Cause:
Alert message if export data called with empty worksheet.

Action:
User should try executing the query or cancel.

BRW-16628
Unable to get printer device. Printing will be unavailable. Continue?

Category:
Other

Cause:
Error creating a toolkit printer surface with uiprc().

Action:
User may continue with no printing or cancel.

BRW-16629
Do you want to update the container before exiting?

Category:
Other

Cause:
Message to prompt user to save changes when closing/quitting OLE doc.

Action:
User may save or abort changes, or cancel.

BRW-16632
No SQL is available because no columns were selected. Quit?

Category:
Other

Cause:
Message to alert user that so sql statement was created.

Action:
User may exit or continue in query builder.

BRW-16650
The printer does not support all fonts needed. Substitute fonts?

Category:
Other

Cause:
The font or some style or weight does not exist for the selected printer.

Action:
User may continue with font substitution or cancel.

BRW-16651
No printer has been chosen. Use Default?

Category:
Other

Cause:
The user has not explicitly named a printer to use.

Action:
User may continue with the system default printer or cancel.

BRW-16652
Margins for this document are too wide and must be reset.

Category:
Other

Cause:
The user has set the margins to be too large leaving no content.

Action:
User must reset the margins.

BRW-16653
No printer has been chosen. Use Default?

Category:
Other

Cause:
The user has not explicitly named a printer to use.

Action:
User may continue with the system default printer or cancel.

BRW-16654
No pages printed.

Category:
Other

Cause:
User has set copies to 0 or the start/end page outside the range.

Action:
Reset page range.

BRW-16660
Query definition has changed. Data may not be current. Re-execute?

Category:
Data

Cause:
Query document has changed since last DDE update.

Action:
Re-execute the query before DDE update, or update without executing.

BRW-16661
Commit changes to %s?

Category:
Other

Cause:
Message to prompt user to commit changes when closing Schema Builder.

Action:
User may commit or abort changes, or cancel.

BRW-16767
Abandon current parameter settings and cancel query?

Category:
Other

Cause:
In parameters dialog, ask user before cancelling settings.

Action:
User may continue the cancel or return to the dialog.

BRW-16776
Apply settings before closing dialog?

Category:
Other

Cause:
Asks user if settings changes should be committed before close.

Action:
User may apply the changes or exit without committing those changes.

BRW-16780
Cannot paste condition on LONG column.

Category:
Other

Cause:
Cannot paste a condition on a long column from the find dialog.

Action:
This action is not supported.

BRW-16807
Accept the definition for the new business area?

Category:
Other

Cause:
Business Area Define - validate Complete NEW business area

Action:
Accept or cancel

BRW-16808
Cancel the incomplete definition for the new business area?

Category:
Other

Cause:
Business Area Define - validate Incomplete NEW business area

Action:
Confirm or cancel

BRW-16809
Accept the modified business area definition?

Category:
Other

Cause:
Business Area Define - validate MODified business area

Action:
Confirm or cancel

BRW-16810
Accept the definition for the new column?

Category:
Other

Cause:
Data Table Expressions - validate Complete NEW expression

Action:
Confirm or cancel

BRW-16811
Cancel the incomplete definition for the new column?

Category:
Other

Cause:
Data Table Expressions - validate Incomplete NEW expression

Action:
Confirm or cancel

BRW-16812
Accept the modified column definition?

Category:
Other

Cause:
Data Table Expressions - validate MODified expression

Action:
Confirm or cancel

BRW-16813
Accept the definition for the new relationship?

Category:
Other

Cause:
Data Table Relationships - validate Complete NEW relationship

Action:
Confirm or cancel

BRW-16816
Accept the changes to the column's format options?

Category:
Other

Cause:
Data Table Format - validate MODified format options

Action:
Confirm or cancel

BRW-16817
Commit changes?

Category:
Other

Cause:
User tries to quit with uncommitted changes

Action:
Confirm or cancel

BRW-16833
Rollback all changes?

Category:
Other

Cause:
Confirmation before rollback

Action:
OK to rollback all changes. Cancel to cancel operation.

BRW-16837
Business area description cannot be empty.

Category:
Other

Cause:
Business area description is null.

Action:
Enter a description.

BRW-16840
Business area name cannot be empty.

Category:
Other

Cause:
Business area name is null.

Action:
enter a name

BRW-16841
Time period definition is incomplete.

Category:
Other

Cause:
Some time period attributes have not been specified.

Action:
Complete the time period definition.

BRW-16852
User is already imported. Reimport?

Category:
Other

Cause:
User has already been imported.

Action:
Confirm or cancel reimport.

BRW-16961
Document '%s' has unsaved publishers.

Category:
Other

Cause:
Message (1 of 2) to prompt user to save changes on close/quit.

Action:
User may save or abort changes, or cancel.

BRW-16962
They will be lost unless the document is saved.

Category:
Other

Cause:
Message (2 of 2) to prompt user to save changes on close/quit

Action:
User may save or abort changes, or cancel.

BRW-16965
Memory is low. Close open documents or restart with more memory.

Category:
Memory

Cause:
Low memory (<1MB)

Action:
Close extra documents, restart with more memory

BRW-16966
Out of memory. Restart application with a larger memory size.

Category:
Memory

Cause:
No memory

Action:
Close extra documents, restart with more memory

BRW-16967
This application requires System 7.0 or higher.

Category:
Other

Cause:
Operating System version is lower than 7.0

Action:
Upgrade operating system and restart

BRW-16975
Cannot resolve data table '{1}'. Select a new data table?

Category:
Data

Cause:
Query Choose Table

Action:
Confirm or cancel

BRW-16976
Cannot resolve column '{1}' in data table '{2}'. Select a new column?

Category:
Data

Cause:
Query Choose Column

Action:
Confirm or cancel

4

CAPTURE-10000 to CAPTURE-10165

CAPTURE-10000
Initializing Capture

Category:
Other

Cause:
The capture application is starting.

Action:
No action required.

CAPTURE-10001
Error creating Batch Item

Category:
Other

Cause:
The user tried adding an item to the batch.

Action:
Make sure there is no problem accessing the database.

CAPTURE-10002
Error committing documents

Category:
Other

Cause:
There was a problem updating the commited column of the document record.

Action:
Make sure the database is accessible and that the user has proper permission to the database tables.

CAPTURE-10003
Error creating workspace

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10004
Error updating workspace

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10005
Error deleting workspace

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10006
Error loading workspaces

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10007
Error creating index definition

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10008
Error loading index definitions

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10009
Error updating index definition

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10010
Error deleting index definition

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10011
Error locating capture object

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10012
Error locating capture object children

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10013
Error loading capture objects

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10014
Error creating batch

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10015
Error updating batch

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10016
The batch lock is no longer valid

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10017
Error deleting batch

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10018
Error finding batch by id

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10019
Error finding batch item by id

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10020
Error loading batches

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10021
Error loading batches by user and workstation

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10022
Error loading batches by user

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10023
Error loading locked batches by user

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10024
Error loading locked batches by workstation

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10025
Error loading locked batches by user and workstation

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10026
Error loading batch items

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10027
Error deleting batch item

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10028
The batch is already locked by ?1 on workstation ?2

Category:
Other

Cause:
The batch is locked by another user

Action:
The batch must be unlocked before it can be locked by somone else

CAPTURE-10029
Error locking batch

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10030
The specified batch has not been persisted or has been deleted by another user.

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10031
Error unlocking batch

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10032
Error creating batch name

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10033
Error creating document

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10034
Error creating db return field

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10035
Error creating db search field

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10036
Error creating db search profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10037
Error loading documents

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10038
Error deleting document

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10039
Error loading documents

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10040
Error linking item to document

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10041
Error unlinking item from document

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10042
Error locating datasource

Category:
Other

Cause:
The data source could not be found

Action:
Ensure the database connection is configured properly and the database is accessible

CAPTURE-10043
Error generating batch id

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10044
Error creating log record

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10045
Error updating capture object

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10046
Error saving database search profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10047
Error deleting object child entities

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10048
Error deleting capture object entity

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10049
Error loading search profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10050
Error loading search profiles

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10051
Error deleting search profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10052
Error loading search fields

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10053
Error loading return fields

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10054
Error deleting return field

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10055
Error deleting search field

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10056
Error saving search field

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10057
Error saving return field

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10058
Error loading database schemas

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10059
Error loading database table fields

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10060
Error loading database tables

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10061
Error executing database lookup

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10062
Error saving document

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10063
Error testing lock

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10064
Error creating extension profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10065
Error loading extension profiles

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10066
Error updating extension profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10067
Error deleting extension profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10068
Error searching for extension profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10069
Error getting batch number

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10070
Error requesting session information

Category:
Other

Cause:
Application configuration error

Action:
The application configuration is invalid or incomplete. Ensure the application is properly configured

CAPTURE-10071
Error moving document pages

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10072
Error splitting document

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10073
Error deleting document pages

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10074
Error creating documents

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10075
Error deleting documents

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10076
Error inserting into documents

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10077
Error searching database

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10078
Error creating bundle entity

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10079
Error loading installed bundles

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10080
Error loading installed bundles by name and version

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10081
Error deleting bundle

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10082
Error updating bundle

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10083
Error during bundle lookup

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10084
Error finding bundle by interface name

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10085
Error scanning for bundles

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10086
Error creating script

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10087
Error loading scripts for product

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10088
Error updating script

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10089
Error deleting script

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10090
Error loading script

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10091
Error loading picklist source

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10092
Error loading picklist link profiles

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10093
Error updating picklist source

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10094
Error creating picklist source

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10095
Error deleting picklist source

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10096
Error loading picklist drivers

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10097
Error finding picklist source

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10098
Error loading picklists

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10099
Error creating picklist

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10100
Error updating picklist

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10101
Error deleting picklist

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10102
Error creating picklist item

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10103
Error loading picklist items

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10104
Error updating picklist items

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10105
Error deleting picklist item

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10106
Error creating picklist link profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10107
Error loading picklist profile links

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10108
Error updating picklist link profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10109
Error deleting picklist link profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10110
Error deleting profile links

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10111
Error linking item to list

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10112
Error unlinking item from list

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10113
Error finding item link

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10114
Error creating Commit Profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10115
Error loading Commit Profiles

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10116
Error updating Commit Profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10117
Error deleting Commit Profile

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10118
Error deleting batch statuses for workspace

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10119
Error deleting index definitions for workspace

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10120
Error deleting batch status from workspace

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10121
A JMS Error has occurred

Category:
Other

Cause:
Diskspace capacity may have been reached.

Action:
Check the disk space capacity and increase as needed.

CAPTURE-10122
Error creating commit profile

Category:
Other

Cause:
The required batch processor could not be created.

Action:
Contact the system administrator.

CAPTURE-10123
Failed to load document types

Category:
Other

Cause:
Database connectivity failure.

Action:
Contact the system administrator.

CAPTURE-10124
The commit driver's configuration is invalid

Category:
Other

Cause:
The commit driver configuration has missing or invalid information

Action:
Verify the configuration settings in the Workspace Management Console.

CAPTURE-10126
Unknown commit error

Category:
Other

Cause:
An unexpected excption was encountered processing the document. This is usually caused by an unhandled exception in the commit driver or export driver.

Action:
Verify the configuration settings in the Workspace Management Console.

CAPTURE-10127
The import processor context must contain a valid DocumentEntity reference

Category:
Other

Cause:
The Import Job may not be properly configured.

Action:
Verify the configuration settings in the Workspace Management Console.

CAPTURE-10128
The import source file is null in the Import Context

Category:
Other

Cause:
The data being imported could not be found.

Action:
Ensure that the Import Processor has privileges to the source file

CAPTURE-10129
The HA token was not found in the import processor context

Category:
Other

Cause:
The Import Processor Context HA Token was missing.

Action:
Ensure that the database server is running.

CAPTURE-10130
The specified workspace could not be found

Category:
Other

Cause:
The Import Processor Context HA Token was missing.

Action:
Ensure that the database server is running.

CAPTURE-10131
Batch [{0}] was successfully locked by user [{1}] batch id is [{2}]

Category:
Other

Cause:
The batch was successfully locked by a user.

Action:
No action required.

CAPTURE-10132
Failed to deliver email

Category:
Other

Cause:
Unable to send email.

Action:
Use the Enterprise Manager to ensure that the Email server settings are correct.

CAPTURE-10133
Error copying workspace

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10134
Commit profile [{0}] does not specifiy a commit driver.

Category:
Other

Cause:
Commit profile configuration problem

Action:
Ensure the specified commit profile has a commit driver specified.

CAPTURE-10135
Commit profile [{0}] does not specifiy an export driver.

Category:
Other

Cause:
Commit profile configuration problem

Action:
Ensure the specified commit profile has an export driver specified.

CAPTURE-10136
Commit profile [{0}] specifies a commit driver that could not be found on the system.

Category:
Other

Cause:
The commit driver specified in the commit profile could not be found.

Action:
Ensure the specified commit driver is properly installed or edit the commit profile and select a different commit driver.

CAPTURE-10137
Commit profile [{0}] specifies an export driver that could not be found on the system

Category:
Other

Cause:
The export driver specified in the commit profile could not be found.

Action:
Ensure the specified export driver is properly installed or edit the commit profile and select a different export driver.

CAPTURE-10138
Unable to create the export directory.

Category:
Other

Cause:
The export driver specified in the commit profile could not be found.

Action:
Ensure the specified export driver is properly installed or edit the commit profile and select a different export driver.

CAPTURE-10139
The following required fields do not have values: [{0}]

Category:
Other

Cause:
Document is missing one or more required fields.

Action:
Ensure all required fields are indexed.

CAPTURE-10140
The batch was routed to a processing job that could not be found

Category:
Other

Cause:
The batch was routed to a job that was not found. The job may have been deleted.

Action:
Ensure that the specified job exists.

CAPTURE-10141
The batch was routed to a processing job that is currently offline

Category:
Other

Cause:
The batch was routed to a job that is in an offline state.

Action:
The job needs to be put in an online state by someone with the required permissions

CAPTURE-10142
A workspace by the specified name already exists.

Category:
Other

Cause:
The user tried to create a workspace using a name that already exists.

Action:
The user should try again using a unique name.

CAPTURE-10143
Error loading locked batches for the specified workspace id

Category:
Other

Cause:
An invalid workspace id was specified or the specified workspace id does not exist.

Action:
Ensure a valid workspace id was specified.

CAPTURE-10144
Method access violation. User {0} attempted to invoke a method they are not authorized to access.

Category:
Other

Cause:
An invocation was made on a method to which the subject was not permitted access.

Action:
Ensure the subject is a member of a secuirity role with permission to invoke the method.

CAPTURE-10145
Unable to send a broadcast email. The SMTP Server connection information is incomplete.

Category:
Other

Cause:
The SMTP server connection information is incomplete

Action:
Use Fusion Middleware Control to configure the SMTP Connection information.

CAPTURE-10146
Document contains no pages.

Category:
Other

Cause:
The document contains no pages

Action:
Review the batch in the capture client and check the system logs for more information.

CAPTURE-10148
Generic commit error.

Category:
Other

Cause:
An error occurred during commit process.

Action:
Check previous log entries for error detail.

CAPTURE-10149
Error duplicating documents.

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database..

CAPTURE-10150
Document Id does not exist.

Category:
Other

Cause:
A document ID was specified but was not found in the database. The document may have been deleted.

Action:
Ensure that the specified document ID exists.

CAPTURE-10151
Index Field [{0}] of Document [{1}] was assigned invalid value [{2}]

Category:
Other

Cause:
An attempt was made to save a document containing an invalid field value. The field may have contained an unprintable character.

Action:
Ensure that only valid printable characters are assigned to document index fields.

CAPTURE-10152
Error loading Import Processor HA Tokens.

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10153
Error loading document type attachment types

Category:
Other

Cause:
Database connectivity failure.

Action:
Contact the system administrator.

CAPTURE-10154
The following required attachment types were not found :[{0}]

Category:
Other

Cause:
Document is missing one or more required attachment types.

Action:
Ensure all required attachment types are provided.

CAPTURE-10155
The source document ID was not found.

Category:
Other

Cause:
The source document ID was not found.

Action:
Ensure document id exists in database.

CAPTURE-10156
An invalid document break point was specified.

Category:
Other

Cause:
An invalid document break point was specified.

Action:
Ensure valid document break point is specified.

CAPTURE-10157
Parent document not found.

Category:
Other

Cause:
Parent document not found.

Action:
Ensure parent document exists.

CAPTURE-10158
The specified database search field is not valid.

Category:
Other

Cause:
The specified database search field is not valid.

Action:
Ensure database search field is valid..

CAPTURE-10159
The specified database search profile is not valid

Category:
Other

Cause:
The specified database search profile is not valid.

Action:
Ensure database search profile is valid.

CAPTURE-10160
The specified workspace is not valid

Category:
Other

Cause:
The specified workspace is not valid

Action:
Ensure workspace is valid.

CAPTURE-10161
The specified source could not be found.

Category:
Other

Cause:
The specified source could not be found.

Action:
Ensure choice list source is valid.

CAPTURE-10162
The source does not specify a valid picklist driver.

Category:
Other

Cause:
The source does not specify a valid picklist driver.

Action:
Ensure choice list driver is valid.

CAPTURE-10163
The driver specified in the source could not be found.

Category:
Other

Cause:
The driver specified in the source could not be found.

Action:
Ensure choice list driver is valid.

CAPTURE-10164
Error copying document pages.

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

CAPTURE-10165
The specified source could not be found.

Category:
Other

Cause:
Database connectivity issue.

Action:
Ensure the database is accessible and the specified user has the necessary permissions to the database.

5
CFGFWK-20836 to CFGFWK-64276

CFGFWK-20836
Test Successful!

Category:
Configuration

Cause:
JDBC connection test was successful.

Action:
No action required.

CFGFWK-20839
Database Load Successful!

Category:
Configuration

Cause:
Database load was successful.

Action:
No action required.

CFGFWK-20840
PointBase Server Started...

Category:
Configuration

Cause:
PointBase server was started successfully.

Action:
No action required.

CFGFWK-20841
PointBase Server Stopped...

Category:
Configuration

Cause:
PointBase server stopped.

Action:
No action required.

CFGFWK-20842
PointBase Server start up message.

Category:
Configuration

Cause:
The PointBase Server instance has been started in the background on port {0}

Action:
No action required.

CFGFWK-20843
Operations cause server stop.

Category:
Configuration

Cause:
Navigating from the panel will cause PointBase server to stop.

Action:
No action required.

CFGFWK-20844
Selected template names.

Category:
Configuration

Cause:
Currently selected templates are {0}

Action:
Information message. No action required.

CFGFWK-20845
Applied templates.

Category:
Configuration

Cause:
Previously applied templates: {0}

Action:
No action required.

CFGFWK-20846
Selected templates.

Category:
Configuration

Cause:
Currently selected templates: {0}

Action:
No action required.

CFGFWK-20847
Template selected.

Category:
Configuration

Cause:
Selecting template {0}:{1} and all its prerequisites.

Action:
Information message. No action required.

CFGFWK-20848
Template loaded.

Category:
Configuration

Cause:
Loading template {0}:{1}.

Action:
Information message. No action required.

CFGFWK-20849
Available templates.

Category:
Configuration

Cause:
Currently available templates for loading: {0}

Action:
No action required.

CFGFWK-20850
The domain is already at the current version.

Category:
Configuration

Cause:
{0}

Action:
Click cancel to exit the wizard.

CFGFWK-40317
Invalid "Servers, Clusters and Machines" configuration.

Category:
Configuration

Cause:
The "Servers, Clusters and Machines" configuration in your domain is invalid.

Action:
Correct the configuration.

CFGFWK-40318
Invalid or missing JDBC datasource connection parameters.

Category:
Configuration

Cause:
The JDBC datasource required parameters are invalid or missing.

Action:
Correct the datasource connection parameters.

CFGFWK-40319
Invalid "JMS" configuration.

Category:
Configuration

Cause:
The "JMS" configuration in your domain is invalid.

Action:
Correct the configuration.

CFGFWK-40320
Invalid "Security" configuration.

Category:
Configuration

Cause:
The "Security" configuration in your domain is invalid.

Action:
Correct the configuration.

CFGFWK-40321
Configuration port conflict.

Category:
Configuration

Cause:
Duplicate Server listen ports exist in your domain configuration: {0}

Action:
Change conflicting ports.

CFGFWK-40322
External port conflict.

Category:
Configuration

Cause:
Server listen ports in your domain configuration conflict with ports in use by active processes on this host: {0}

Action:
Change conflicting ports.

CFGFWK-40323
Invalid configuration.

Category:
Configuration

Cause:
A section of configuration in your domain is invalid.

Action:
Correct the configuration.

CFGFWK-40324
Invalid "JMS" configuration.

Category:
Configuration

Cause:
JMSDestination's JNDI names are not unique in same target.

Action:
Correct the configuration.

CFGFWK-40325
Invalid "JDBC" configuration.

Category:
Configuration

Cause:
JDBC JNDI names are not unique in the same target.

Action:
Correct the configuration.

CFGFWK-40326
Invalid coherence server address.

Category:
Configuration

Cause:
At least one server in a Coherence cluster should have non localhost address.

Action:
Enter a non localhost listen address for at least one Coherence server.

CFGFWK-40327
Non supported configuration for restricted mode exists.

Category:
Configuration

Cause:
Non supported configuration for restricted mode like config mapping exists.

Action:
Restricted templates should not include non supported configuration.

CFGFWK-40865
The text in the file has changed.

Category:
Configuration

Cause:
This file has been modified in the editor, discard changes?

Action:
Confirm to discard the changes.

CFGFWK-40866
Discard previous changes.

Category:
Configuration

Cause:
Discard previously saved changes?

Action:
Confirm to discard changes.

CFGFWK-40867
Discard the changes.

Category:
Configuration

Cause:
Edited file has been modified, discard changes?

Action:
Confirm to discard changes.

CFGFWK-40868
No system component instance

Category:
Configuration

Cause:
You have not created any system component.

Action:
Create a system component.

CFGFWK-40891
A Custom directory doesn't contain valid JDK.

Category:
Configuration

Cause:
Unable to determine if the specified directory contains a valid JDK.

Action:
Specify a directory with valid JDK.

CFGFWK-40893
Invalid JDK Version.

Category:
Configuration

Cause:
The selected JDK version doesn't match the jdk version pattern.

Action:
Select a different JDK.

CFGFWK-40894
Invalid minimum JDK Version.

Category:
Configuration

Cause:
The recommended minimum JDK version doesn't match the JDK version pattern.

Action:
Enter a valid JDK directory.

CFGFWK-40895
Invalid JDK Version.

Category:
Configuration

Cause:
The selected JDK version is lower than recommended minimum version.

Action:
Enter a valid JDK directory.

CFGFWK-40896
Use of production mode instead of secure

Category:
Configuration

Cause:
Oracle recommends that you select the Secure option for Production mode.

Action:
Please check the secure mode to have a secure domain in the Production environment.

CFGFWK-40905
Template exists.

Category:
Configuration

Cause:
A template already exists in that location. Do you want to overwrite it?

Action:
Select the desired answer.

CFGFWK-40906
Node Manager configuration will be skipped.

Category:
Configuration

Cause:
Oracle recommends using per domain Node Manager configuration. Current selection will cause the configuration of Node Manager for the domain to be skipped.

Action:
Continue configuration to skip the current node manager configuration.

CFGFWK-40915
JMS system resource selected for conversion to a UDD

Category:
Configuration

Cause:
At least one JMS system resource has been selected for conversion to a Uniform Distributed Destination (UDD). This conversion will take place only if the JMS system resource is assigned to a cluster.

Action:
Warning message. No action required.

CFGFWK-40930
Oracle Home not set

Category:
Configuration

Cause:
Oracle Home is not set for the current configuration.

Action:
Set Oracle Home.

CFGFWK-40931
No domain information.

Category:
Configuration

Cause:
Unable to obtain information pertaining to current domain.

Action:
Provide domain information.

CFGFWK-40950
Reconfiguration template was not available for custom template, and original not found; start scripts may be incomplete

Category:
Configuration

Cause:
The custom template at {0} had no corresponding reconfiguration template, and the original template could not be found.

Action:
Check start scripts and manually edit to add contributions from the custom template.

CFGFWK-40951
An application or library was not relocated to the new MW home.

Category:
Configuration

Cause:
Custom Applications were left in the original MW home and must be fixed manually: {0}

Action:
Correct source path of the applications to refer to the new installation.

CFGFWK-42001
Configuration conflicts detected.

Category:
Configuration

Cause:
Duplicate elements were found in configuration: {0}

Action:
No action required. Elements from an incoming template will be discarded.

CFGFWK-42057
No templates installed.

Category:
Configuration

Cause:
Installation contains no standard templates.

Action:
Check installation or use custom template if available.

CFGFWK-42061
Configuration component conflict detected.

Category:
Configuration

Cause:
The selected template contains a component already defined in the existing domain.

Action:
Indicate how to resolve this conflict.

CFGFWK-42062
Unable to select template.

Category:
Configuration

Cause:
The {0} template could not be selected because of the following: {1}.

Action:
Fix the problems which prevented template selection, then try again.

CFGFWK-42063
Unable to unselect template.

Category:
Configuration

Cause:
The {0} template could not be unselected because of the following: {1}.

Action:
Fix the problems which prevented template unselected, then try again.

CFGFWK-42064
Hidden selected templates.

Category:
Configuration

Cause:
One or more of the templates you selected are no longer visible in the list of Available Templates. To see all the templates you selected, select All Templates from the Template Categories menu.

Action:
Select "All Templates" from the Template Categories menu.

CFGFWK-42065
Missing driver classes.

Category:
Configuration

Cause:
The driver classes listed below were not found in the product installation: {0} A test will not be performed for any database connections using these drivers.

Action:
Provide driver class.

CFGFWK-42066
Missing driver class.

Category:
Configuration

Cause:
The driver class listed below was not found in the product installation: {0} A test will not be performed for any database connections using this driver.

Action:
Provide driver class.

CFGFWK-42067
The JDBC configuration test did not fully complete or completed with errors.

Category:
Configuration

Cause:
See "Connection Result Log" for details

Action:
You can click "Next" to bypass the testing or go back to the previous panels to fix the problems. If Data Guard is used, the check is expected to fail for standby addresses, and the warning can be ignored.

CFGFWK-42068
The schema component data are not bound or the binding operation is unsuccessful with errors.

Category:
Configuration

Cause:
Error message: {0}.

Action:
Enter the correct database connection parameters.

CFGFWK-60001
User name contains unsupported characters.

Category:
Configuration

Cause:
The user name contains commas, tabs, spaces, or any of the following characters: <>#|&?(){}

Action:
Remove unsupported characters.

CFGFWK-60005
Invalid password.

Category:
Configuration

Cause:
WebLogic domain requires the password to be minimum 8 characters

Action:
Provide valid password.

CFGFWK-60052
Class name contains spaces.

Category:
Configuration

Cause:
Space characters are not allowed.

Action:
Correct the class name.

CFGFWK-60055
Duplicated value.

Category:
Configuration

Cause:
The property "{0}" value is duplicated.

Action:
Remove the duplicates.

CFGFWK-60058
Invalid class name.

Category:
Configuration

Cause:
The class name must have the format "xxx.xxx.xxx.xxx".

Action:
Correct the class name.

CFGFWK-60062
Additional address disallowed.

Category:
Configuration

Cause:
Invalid {0} of {1} "{2}". If "All Local Addresses" is selected, no additional address should be provided.

Action:
Remove additional address.

CFGFWK-60063
No listen address is provided.

Category:
Configuration

Cause:
Invalid {0} of {1} "{2}". The list of address is empty.

Action:
Provide at least one address.

CFGFWK-60064
Mismatched passwords.

Category:
Configuration

Cause:
The confirmation password does not match the entered password.

Action:
Correct the password.

CFGFWK-60150
Servers port conflict.

Category:
Configuration

Cause:
The server "{0}" has the same combination of listen address and port as server "{1}".

Action:
Select different port value.

CFGFWK-60151
SSL port conflict.

Category:
Configuration

Cause:
The server "{0}" has the same combination of listen address and SSL port as server "{1}".

Action:
Select different SSL port value.

CFGFWK-60152
Admin port conflict.

Category:
Configuration

Cause:
The server "{0}" has the same combination of listen address and port as admin server.

Action:
Select a different port.

CFGFWK-60153
Admin SSL port conflict.

Category:
Configuration

Cause:
The server "{0}" has the same combination of listen address and SSL port as admin server.

Action:
Select a different port.

CFGFWK-60154
Server port conflict.

Category:
Configuration

Cause:
The server "{0}" has the same port and SSL port.

Action:
Set one of the ports to a different value.

CFGFWK-60155
Empty Listen Port.

Category:
Configuration

Cause:
Server "{0}" Listen Port is empty.

Action:
Set Listen Port.

CFGFWK-60156
IP v6 address in a wrong format.

Category:
Configuration

Cause:
The IP address must have the proper v6 format like "xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx" or "xxxx:xxxx:xxxx:xxx:xxx.xxx.xxx.xxx" or other supported format.

Action:
Correct the IP address.

CFGFWK-60157
IP address in a wrong format.

Category:
Configuration

Cause:
The IP address must have the format "xxx.xxx.xxx.xxx".

Action:
Correct the IP address.

CFGFWK-60158
Invalid IP address segment.

Category:
Configuration

Cause:
Each segment of the IP address must contain an integer in the range of 0 to 255.

Action:
Correct the IP address.

CFGFWK-60159
Invalid IP address segment.

Category:
Configuration

Cause:
Each segment of the IP address must contain an integer in the range of 0 to 255.

Action:
Correct the IP address.

CFGFWK-60160
Multicast IP address out of range.

Category:
Configuration

Cause:
The IP multicast address must be in the range of 224.0.0.1 to 239.255.255.255.

Action:
Correct the IP address.

CFGFWK-60161
Invalid host name.

Category:
Configuration

Cause:
The host name does not allow leading or trailing dot (.).

Action:
Correct the host name.

CFGFWK-60162
Invalid host name.

Category:
Configuration

Cause:
The host name does not allow multiple dots (.).

Action:
Correct the host name.

CFGFWK-60163
Invalid host name.

Category:
Configuration

Cause:
No member of the hostname may begin or end with a dash (-).

Action:
Correct the host name.

CFGFWK-60164
Invalid host name.

Category:
Configuration

Cause:
The entered value is not a valid hostname. Please use only alphanumeric characters and dot (.) and dash (-).

Action:
Correct the host name.

CFGFWK-60165
Invalid Host Address.

Category:
Configuration

Cause:
Host address allows only digits.

Action:
Correct the host address.

CFGFWK-60166
Invalid address format.

Category:
Configuration

Cause:
Each entry must be expressed as <hostname> or <hostname>:<port>.

Action:
Correct the hostname and port format.

CFGFWK-60167
Invalid port.

Category:
Configuration

Cause:
The port number must be an integer.

Action:
Correct the port.

CFGFWK-60168
Invalid port.

Category:
Configuration

Cause:
The port number must be an integer in the range of 1 to 65535.

Action:
Correct the port.

CFGFWK-60169
Conflicting multicast ports.

Category:
Configuration

Cause:
The cluster has the same combination of multicast address and port as other cluster.

Action:
Change address or port for one of the clusters.

CFGFWK-60170
Invalid multicast port.

Category:
Configuration

Cause:
Multicast port cannot be empty.

Action:
Provide valid port value.

CFGFWK-60171
Conflicting machine definitions.

Category:
Configuration

Cause:
The machine "{0}" has the same combination of listen address and port as other machine "{1}".

Action:
Change one of machine definitions.

CFGFWK-60172
Invalid listen port.

Category:
Configuration

Cause:
Listen port cannot be empty.

Action:
Provide valid port value.

CFGFWK-60173
Port conflict.

Category:
Configuration

Cause:
The admin server listen address "{0}" and port "{1,number,#}" conflicts with ports in use by existing processes on current host.

Action:
Select a different port.

CFGFWK-60174
SSL port conflict.

Category:
Configuration

Cause:
The admin server SSL listen address "{0}" and port "{1,number,#}" conflicts with ports in use by existing processes on current host.

Action:
Select a different port.

CFGFWK-60175
Empty SSL Listen Port.

Category:
Configuration

Cause:
Server "{0}" SSL Listen Port is empty.

Action:
Set SSL Listen Port.

CFGFWK-60176
Invalid IP address segment.

Category:
Configuration

Cause:
Invalid {0} of {1} "{2}". Please enter a valid hostname or IP address. Note that if you are entering a IP address, Each segment of the IP address must contain an integer in the range of 0 to 255.

Action:
Correct the IP address.

CFGFWK-60177
System component type is not specified.

Category:
Configuration

Cause:
System component type can not be empty.

Action:
Enter a valid system component type.

CFGFWK-60178
Only system component types "{0}" are supported.

Category:
Configuration

Cause:
Only system component types "{0}" are supported.

Action:
Enter a valid system component type.

CFGFWK-60179
Invalid OHS instance name "{0}".

Category:
Configuration

Cause:
The following OHS instance names are not valid, regardless of lower or upper case: "mbeans", "domain_bak", "instances", "AdminServer", "AdminServerTag".

Action:
Enter a valid OHS instance name.

CFGFWK-60180
Invalid OHS instance name "{0}".

Category:
Configuration

Cause:
OHS instance names must begin with an alphabetic character, contain only alpha-numerics, underscores, and hyphens, and be no more than 30 characters long.

Action:
Enter a valid OHS instance name.

CFGFWK-60181
Conflicting machine definition.

Category:
Configuration

Cause:
The machine "{0}" has the same combination of listen address and port as other server "{1}".

Action:
Change machine definitions.

CFGFWK-60182
Conflicting server definition.

Category:
Configuration

Cause:
The server "{0}" has the same combination of listen address and port as machine "{1}".

Action:
Change server definition.

CFGFWK-60200
Invalid targeting for distributed destination.

Category:
Configuration

Cause:
The targets of the distributed destination should cover all the servers that host the members.

Action:
Include the missing servers.

CFGFWK-60201
The distributed topic is not deployed.

Category:
Configuration

Cause:
The distributed topic "{0}" that distributed topic member "{1}" belongs to is not deployed.

Action:
Deploy the distributed topic.

CFGFWK-60202
The JMS server is not deployed.

Category:
Configuration

Cause:
The JMS Server "{0}" that topic "{1}" belongs to is not deployed.

Action:
Deploy the JMS server.

CFGFWK-60203
The distributed queue is not deployed.

Category:
Configuration

Cause:
The distributed queue "{0}" that distributed queue member "{1}" belongs to is not deployed.

Action:
Deploy distributed queue.

CFGFWK-60204
The JMS server is not deployed

Category:
Configuration

Cause:
The JMS Server "{0}" that queue "{1}" belongs to is not deployed.

Action:
Deploy the JMS server.

CFGFWK-60205
Empty group with Admin role.

Category:
Configuration

Cause:
Group(s) assigned to "Admin" role must contain at least one user.

Action:
Add user to group.

CFGFWK-60206
Unassigned Admin role.

Category:
Configuration

Cause:
Admin role must be assigned at least one group or one user.

Action:
Assign Admin role to a group or a user.

CFGFWK-60209
JDBCConnectionPool undeployment failure.

Category:
Configuration

Cause:
The JDBCConnectionPool "{0}" could not be undeployed from target "{1}", because it is used by the JMSJDBCStore "{2}", which is used by the deployed JMSServer "{3}".

Action:
Switch JMSJDBCStore to use a different JDBCConnectionPool.

CFGFWK-60250
Duplicate JNDI name.

Category:
Configuration

Cause:
The JNDI name is duplicated in JMS server "{0}"

Action:
Choose a different JNDI name.

CFGFWK-60300
Domain name missing.

Category:
Configuration

Cause:
Domain name is not specified.

Action:
Specify the domain name.

CFGFWK-60301
Domain name conflict.

Category:
Configuration

Cause:
The name of the WebLogic domain and the server and cluster names within it must be unique. A server or cluster already exists with the WebLogic domain name you specified.

Action:
Change the name of the domain, conflicting server or cluster.

CFGFWK-60302
Domain already exists.

Category:
Configuration

Cause:
A domain already exists at the specified location.

Action:
Change the domain location.

CFGFWK-60303
Domain directory is not empty.

Category:
Configuration

Cause:
The domain directory "{0}" you specified contains files. You may only create a domain in an empty directory.

Action:
Pick a different domain location.

CFGFWK-60304
Applications directory is not empty.

Category:
Configuration

Cause:
The applications directory "{0}" that you specified contains files. Applications may only be written to an empty directory.

Action:
Pick a different directory.

CFGFWK-60305
Invalid domain name.

Category:
Configuration

Cause:
The specified domain name is invalid. It must include only alphanumeric characters, hyphens ('-') or underscore characters ('_') and contain at least one letter but must not start with a number.

Action:
Correct the domain name.

CFGFWK-60306
Domain location contains spaces.

Category:
Configuration

Cause:
The domain location contains spaces.

Action:
Remove space characters.

CFGFWK-60307
Domain location is missing.

Category:
Configuration

Cause:
The domain location is not be specified.

Action:
Specify the domain location.

CFGFWK-60308
Domain location not writable.

Category:
Configuration

Cause:
The domain location does not have write permission.

Action:
Correct permissions or select different domain location.

CFGFWK-60309
Applications location contains spaces.

Category:
Configuration

Cause:
The applications location contains spaces.

Action:
Remove space characters.

CFGFWK-60310
Applications location missing.

Category:
Configuration

Cause:
The applications location is not specified.

Action:
Specify applications location.

CFGFWK-60311
Applications location not writable.

Category:
Configuration

Cause:
The applications location does not have write permission.

Action:
Correct permissions or select different location.

CFGFWK-60312
Template name missing.

Category:
Configuration

Cause:
Template name is not specified.

Action:
Specify the template name.

CFGFWK-60313
Invalid template name.

Category:
Configuration

Cause:
The specified template name is invalid. It must include only alphanumeric characters, hyphens ('-') or underscore characters ('_') and contain at least one letter or digit.

Action:
Correct the template name.

CFGFWK-60314
Template location contains spaces.

Category:
Configuration

Cause:
The template location contains spaces.

Action:
Remove space characters.

CFGFWK-60315
Template location missing.

Category:
Configuration

Cause:
The template location is not specified.

Action:
Specify template location.

CFGFWK-60316
Template location not writable.

Category:
Configuration

Cause:
The template location does not have write permission.

Action:
Correct permissions or select different location.

CFGFWK-60317
The name of the domain, server or cluster names must be unique.

Category:
Configuration

Cause:
A domain or cluster already exists with the Server name.

Action:
Change the name of the domain, conflicting server or cluster.

CFGFWK-60324
Location is not a directory.

Category:
Configuration

Cause:
The given location is not a directory.

Action:
Provide a valid location.

CFGFWK-60325
Invalid location.

Category:
Configuration

Cause:
The directory location is invalid.

Action:
Provide a valid location.

CFGFWK-60326
Invalid directory location.

Category:
Configuration

Cause:
The specified directory location is invalid. It must include only alphanumeric characters, hyphens ('-') or underscore characters ('_') and contain at least one letter or digit.

Action:
Correct the location.

CFGFWK-60327
Location is missing.

Category:
Configuration

Cause:
Location is not provided.

Action:
Specify the location.

CFGFWK-60328
Invalid applications directory.

Category:
Configuration

Cause:
The applications location is not a directory.

Action:
Provide a valid directory.

CFGFWK-60329
Missing KeyStore password.

Category:
Configuration

Cause:
The following templates require entry of a KeyStore password:

Action:
Set password for affected templates.

CFGFWK-60330
KeyStore information missing.

Category:
Configuration

Cause:
Some of the added template require KeyStore information.

Action:
Use the storeKeyStorePassword(template_location, password) command for each template listed above to enter required KeyStore passwords. The command must be entered after adding templates and before updating the domain.

CFGFWK-60331
The domain location path is not absolute.

Category:
Configuration

Cause:
The path of the domain location field is not absolute.

Action:
Correct path or select different location.

CFGFWK-60332
The application location path is not absolute.

Category:
Configuration

Cause:
The path of the application location field is not absolute.

Action:
Correct path or select different location.

CFGFWK-60333
Node Manager location contains spaces.

Category:
Configuration

Cause:
The Node Manager location contains spaces.

Action:
Remove space characters.

CFGFWK-60334
Node Manager location is missing.

Category:
Configuration

Cause:
The Node Manager location is not be specified.

Action:
Specify the Node Manager location.

CFGFWK-60335
The Node Manager location path is not absolute.

Category:
Configuration

Cause:
The path of the Node Manager location field is not absolute.

Action:
Correct path or select different location.

CFGFWK-60336
Location is not a directory.

Category:
Configuration

Cause:
The given location is not a directory.

Action:
Provide a valid location.

CFGFWK-60337
Node Manager location not writable.

Category:
Configuration

Cause:
The Node Manager location does not have write permission.

Action:
Correct permissions or select different domain location.

CFGFWK-60338
Non supported distributed topic exists.

Category:
Configuration

Cause:
As part of JMS expansion JMS topics were converted to replicated distributed topics (RDTs) to preserve backward compatible behavior. The JMSServers targeted to dynamic clusters do not currently support RDT topics. The support is only available for partition distributed topics (PDT). Because PTD behavior is different from RTD an explicit property needs to be passed to the process to indicate that the conversion is intentional. Use system property "-Dcie.jms.internal.temp.expansion.use.pdt=true" to generate partitioned distributed topic.

Action:
Use system property "-Dcie.jms.internal.temp.expansion.use.pdt=true" to generate partitioned distributed topic as default is replicated distributed topic.

CFGFWK-60339
Machine and Node Manager is not configured.

Category:
Configuration

Cause:
An attempt was made to set the migration-policy of Persistent Store to "On-Failure" or "Alwyas". Before automatic migration of any kind can be used, the MigrationBasis must be set in the ClusterMBean. If database is chosen as MigrationBasis, then DataSourceForAutomaticMigration must be set as well.When consensus leasing is chosen as MigrationBasis, all servers that belong to the cluster must have a machine set and nodemanager configured for that machine.

Action:
Set machine and configure nodemanager for that machine.

CFGFWK-60340
A cluster member is being individually targeted via VirtualTarget.

Category:
Configuration

Cause:
A Managed server cannot be a member of cluster and individually targeted using VirtualTarget. The following VirtualTargets cannot be targeted individually {0}.

Action:
The clustered Managed server VirtualTarget should not be used for targeting.

CFGFWK-60341
Calculated Machine Names or Machine and Node Manager is not configured.

Category:
Configuration

Cause:
Some Oracle Fusion Middleware Products require calculated machine names to be selected and Machine and Node Manager to be configured unless Front-End Host is used.

Action:
Set calculated machine names attribute, machines and configure nodemanager for that machine.

CFGFWK-60450
Attempt to delete admin user.

Category:
Configuration

Cause:
The default admin user could not be deleted.

Action:
Operation aborted. No further actions required.

CFGFWK-60451
Attempt to add restricted groups.

Category:
Configuration

Cause:
Cannot add built-in groups "everyone" or "users".

Action:
Operation aborted. No further actions required.

CFGFWK-60452
Missing roles.

Category:
Configuration

Cause:
Built-in roles "Admin" and "Anonymous" must be provided.

Action:
Provide required roles.

CFGFWK-60453
Password too short.

Category:
Configuration

Cause:
The supplied user password for "{0}" is too short.

Action:
Provide valid password.

CFGFWK-60454
Password too short.

Category:
Configuration

Cause:
The supplied user password for "{0}" is too short.

Action:
Provide valid password.

CFGFWK-60455
Invalid password.

Category:
Configuration

Cause:
The password must be at least 8 alphanumeric characters with at least one number or special character.

Action:
Correct the password.

CFGFWK-60456
Invalid or missing credentials configuration.

Category:
Configuration

Cause:
The credentials configuration in your domain is invalid.

Action:
Correct the configuration.

CFGFWK-60457
Invalid or missing keystore configuration.

Category:
Configuration

Cause:
The keystore configuration in your domain is invalid.

Action:
Correct the configuration.

CFGFWK-60458
Invalid private key password.

Category:
Configuration

Cause:
The password must be the same, used to create a private key.

Action:
Correct the private key password.

CFGFWK-60550
Script execution aborted.

Category:
Configuration

Cause:
Encountered error: "{0}". Error is logged to "{1}".

Action:
See log for details.

CFGFWK-60600
Missing domain security.

Category:
Configuration

Cause:
Before booting this domain, it is necessary to run the SQL file located at {0} in order to initialize a domain security admin user in the database.

Action:
Execute the SQL file.

CFGFWK-60707
Template already selected.

Category:
Configuration

Cause:
The template "{0}" is already selected.

Action:
No action required. The template is ignored.

CFGFWK-60708
Template not found.

Category:
Configuration

Cause:
Found no templates with {0} name and {1} version

Action:
Select a different template.

CFGFWK-60709
Multiple matching templates.

Category:
Configuration

Cause:
Found {2} templates with {0} name and {1} version.

Action:
Possibly corrupted installation. Check installation for correctness.

CFGFWK-60710
Template not selected.

Category:
Configuration

Cause:
No templates were selected!

Action:
Select templates to load.

CFGFWK-60711
Template loading failed.

Category:
Configuration

Cause:
Unable to load template with {0} name and {1} version: {2}.

Action:
Check the logs for more information.

CFGFWK-60712
Template loading failed.

Category:
Configuration

Cause:
Unable to load template from [{0}].

Action:
Provide valid path.

CFGFWK-60713
Command execution failed.

Category:
Configuration

Cause:
Attempt to execute command "{0}" in invalid state: {1}

Action:
Check the logs for more information.

CFGFWK-60714
Method not present.

Category:
Configuration

Cause:
The method "{0}" is not available.

Action:
Provide valid method.

CFGFWK-60716
The domain contains online pending unactivated changes, offline changes will be ignored on activation of pending changes.

Category:
Configuration

Cause:
The domain contains online pending unactivated changes.

Action:
Activate or undo the pending changes before upgrading domain using WLST offline script.

CFGFWK-60717
No supported Database for datasource or schema component

Category:
Configuration

Cause:
When merging database.xml in templates, there was no common database type that supported all of the usages of the datasource or schema component {0}.

Action:
Remove conflicting templates from list of selected templates being added to the domain.

CFGFWK-60718
Datasource does not use a database supported by the existing configuration

Category:
Configuration

Cause:
One of the templates added to the domain does not support the configured database type used by the datasource or component {0}.

Action:
Remove conflicting templates from list of selected templates being added to the domain, or migrate the datasource to a database that supports the required extension.

CFGFWK-60800
Bad Template

Category:
Configuration

Cause:
There is a problem with the template

Action:
Correct the template

CFGFWK-60806
Error when generating log file

Category:
Configuration

Cause:
The Configuration Wizard was unable to generate the log file located at

Action:
Check the log file.

CFGFWK-60808
Unsupported Domain

Category:
Configuration

Cause:
Only domains associated with Oracle Home {0} are eligible for update..

Action:
Select a domain from the currently active middleware home.

CFGFWK-60816
Unsupported Template

Category:
Configuration

Cause:
The template {0} is not supported in the current environment as it was created without the presence of application server.

Action:
Select a template created from the environment without the presence of an application server

CFGFWK-60817
Unsupported Template

Category:
Configuration

Cause:
The template {0} is not supported in the current environment which requires the presence of an application server.

Action:
Select a template created from the environment containing an application server

CFGFWK-60818
Unsupported Domain

Category:
Configuration

Cause:
The domain {0} is not supported in the current environment as it was created without the presence of application server.

Action:
Select a domain created without the presence of application server

CFGFWK-60819
Unsupported Domain

Category:
Configuration

Cause:
The domain {0} is not supported in the current environment which requires the presence of an application server.

Action:
Select a domain created from the environment containing an application server

CFGFWK-60820
Unsupported Domain

Category:
Configuration

Cause:
This domain is a managed domain. It has been scaled out from the original domain.

Action:
Select a domain which is a compatible with this environment.

CFGFWK-60825
Error in HTTP proxy Application

Category:
Configuration

Cause:
Unable to create HTTP proxy application(s)

Action:
Check the configuration.

CFGFWK-60826
Existing Proxy

Category:
Configuration

Cause:
You have chosen a managed server {0} which is already a proxy for a cluster.

Action:
It is recommended that a managed server only proxy a single cluster.

CFGFWK-60827
Invalid Host name or IP address for managed Server

Category:
Configuration

Cause:
The managed server {0} chosen as a HTTP proxy for the cluster has an invalid Host name or IP address.

Action:
The managed server should have a valid host name or an IP address.

CFGFWK-60828
Invalid Host name for Server

Category:
Configuration

Cause:
The server {0}, which is assigned to the cluster {1} has an invalid Host name or IP address.

Action:
The Listen Address for all servers in a cluster with an HTTP proxy should be a valid host name or an IP address.

CFGFWK-60829
Invalid managed Server

Category:
Configuration

Cause:
The managed server with the server Name {0} chosen as a HTTP proxy for a cluster does not exist.

Action:
The managed server should exist and be valid.

CFGFWK-60830
No file to load.

Category:
Configuration

Cause:
There must be files to load.

Action:
Provide file to load.

CFGFWK-60831
No file selected.

Category:
Configuration

Cause:
You must select a file first.

Action:
Select a file.

CFGFWK-60834
Invalid URL.

Category:
Configuration

Cause:
The URL entered may not end with forward slash ("/").

Action:
Modify the URL.

CFGFWK-60835
Invalid URL.

Category:
Configuration

Cause:
The URL entered was malformed: {0}

Action:
Modify the URL.

CFGFWK-60837
Test failed.

Category:
Configuration

Cause:
Test Failed!

Action:
Check the log.

CFGFWK-60838
Error in connection.

Category:
Configuration

Cause:
Error getting connection information!

Action:
Check the log.

CFGFWK-60839
Failed to load database.

Category:
Configuration

Cause:
Database Load Failed!

Action:
Check the log.

CFGFWK-60840
Error in PointBase server startup.

Category:
Configuration

Cause:
Error encountered starting PointBase server or the server process was killed!

Action:
Check the log.

CFGFWK-60841
Log path.

Category:
Configuration

Cause:
For possible information regarding the error check the log located at:

Action:
Check the log.

CFGFWK-60842
Error in stopping PointBase server.

Category:
Configuration

Cause:
Error encountered stopping the PointBase server! Check log file:

Action:
Check the log.

CFGFWK-60843
Error in writing log file.

Category:
Configuration

Cause:
Error Writing Log File:

Action:
Check the log.

CFGFWK-60855
Invalid Template Name.

Category:
Configuration

Cause:
The Template Name is blank.

Action:
Enter a valid Template Name.

CFGFWK-60856
Invalid Template Version.

Category:
Configuration

Cause:
The Template Version is blank.

Action:
Enter a valid Template Version.

CFGFWK-60857
Invalid Template Version Number.

Category:
Configuration

Cause:
The Template Version Number is invalid. It should be in the format N.N.N.N.N or N.N.N.N where N is a whole number.

Action:
Enter a valid Template Version Number.

CFGFWK-60865
Can not edit the file.

Category:
Configuration

Cause:
This file type is not editable

Action:
Provide writable permission to file.

CFGFWK-60870
Invalid start or end character for path.

Category:
Configuration

Cause:
Path cannot start or end with a path separator.

Action:
Remove the path separator at the start or end

CFGFWK-60875
Invalid selection for removal

Category:
Configuration

Cause:
The selected directory is a representation of a location that will be selected by the user when using this configuration and cannot be removed.

Action:
Select another file or directory to remove

CFGFWK-60876
Invalid selection for removal

Category:
Configuration

Cause:
You cannot remove the files in red or their parent directories because they comprise this configuration's applications.

Action:
Select another file or directory to remove

CFGFWK-60877
No file selected to be removed

Category:
Configuration

Cause:
You must first select a file to remove.

Action:
Select a file to be removed

CFGFWK-60878
Not selected Source file or directory

Category:
Configuration

Cause:
You must select a source file or directory on the left

Action:
Select a valid source file or directory

CFGFWK-60879
Invalid destination location

Category:
Configuration

Cause:
You must select a destination location on the right

Action:
Select a destination location

CFGFWK-60880
Invalid selection

Category:
Configuration

Cause:
The selected directory is a representation of a location that will be selected by the user when using this configuration and files cannot be added.

Action:
Select another destination file or directory

CFGFWK-60881
Invalid selection

Category:
Configuration

Cause:
The selected file cannot be added to your domain directory because it is a reserved file. This usually means that the file will be auto-generated by the configuration wizard and does not need to be added.

Action:
Select a different file or directory

CFGFWK-60882
Error reading template location.

Category:
Configuration

Cause:
The template location {0} cannot be read due to an unexpected I/O error.

Action:
Verify template location is a valid one.

CFGFWK-60885
Error preparing the template

Category:
Configuration

Cause:
Error encountered preparing template from jar

Action:
Check the jar file.

CFGFWK-60891
A Custom directory doesn't contain valid JDK.

Category:
Configuration

Cause:
Unable to determine if the specified directory contains a valid JDK. Do you want to proceed?

Action:
Specify a directory with valid JDK.

CFGFWK-60892
Invalid directory location

Category:
Configuration

Cause:
The specified directory does not exist.

Action:
Enter a valid JDK directory.

CFGFWK-60900
No file selected

Category:
Configuration

Cause:
No file was selected to be moved up

Action:
Select a file to be moved up

CFGFWK-60901
No file selected

Category:
Configuration

Cause:
No file was selected to be moved down

Action:
Select a file to be moved down

CFGFWK-60905
Password mismatch.

Category:
Configuration

Cause:
Password does not match.

Action:
Correct the password.

CFGFWK-60906
Empty field.

Category:
Configuration

Cause:
The field {0} cannot be empty.

Action:
Provide field value.

CFGFWK-60907
Invalid field value.

Category:
Configuration

Cause:
The field {0} must be an integer.

Action:
Provide integer value.

CFGFWK-60908
Empty password field.

Category:
Configuration

Cause:
The password/confirm password field is empty.

Action:
Provide value for password/confirm password field.

CFGFWK-60909
Password does not match.

Category:
Configuration

Cause:
The password entered should match the confirm password field.

Action:
Correct the password.

CFGFWK-60915
Invalid custom directory.

Category:
Configuration

Cause:
A Custom directory is not empty.

Action:
Specify a valid directory.

CFGFWK-60916
Invalid node manager home

Category:
Configuration

Cause:
The node manager home is not a directory.

Action:
Specify a valid directory.

CFGFWK-60918
Invalid user name

Category:
Configuration

Cause:
The user name can not be empty.

Action:
Specify a valid user name.

CFGFWK-60919
Invalid SSL Listen Port.

Category:
Configuration

Cause:
SSL Listen Port of Server "{2}" is empty.

Action:
Provide SSL Listen Port value.

CFGFWK-60920
The name of the domain, server or cluster names must be unique.

Category:
Configuration

Cause:
A domain or server already exists with the Cluster name "{2}".

Action:
Change the name of the domain, conflicting server or cluster.

CFGFWK-60921
The name of the domain, server or cluster names must be unique.

Category:
Configuration

Cause:
A domain or cluster already exists with the Server name "{2}".

Action:
Change the name of the domain, conflicting server or cluster.

CFGFWK-60922
Invalid port value.

Category:
Configuration

Cause:
The listen port value {3,number,#} of {1} "{2}" is out of range. It must be between 1 and 65535.

Action:
Enter a valid port value.

CFGFWK-60923
Invalid port value.

Category:
Configuration

Cause:
The SSL listen port value {3,number,#} of Server "{2}" is out of range. It must be between 1 and 65535.

Action:
Enter a valid port value.

CFGFWK-60924
Invalid value of "{0}" property.

Category:
Configuration

Cause:
Property "{0}" of {1} "{2}" is invalid. The name must not be null or empty and may not contain any : , = * ? % / _cloned.

Action:
Provide valid property value.

CFGFWK-60925
Invalid port value.

Category:
Configuration

Cause:
The Coherence listen port value {1,number,#} of cluster "{0}" is out of range. It must be between 0 and 65535.

Action:
Enter a valid port value.

CFGFWK-60926
Invalid port value.

Category:
Configuration

Cause:
The listen port value {3,number,#} of node manager for machine "{2}" is out of range. It must be between 1 and 65534.

Action:
Enter a valid port value.

CFGFWK-60927
Invalid port value.

Category:
Configuration

Cause:
The Coherence listen port value {1,number,#} of cluster "{0}" is invalid. It must be between 0 and 65535.

Action:
Enter a valid port value.

CFGFWK-60928
Invalid existing node manager home directory.

Category:
Configuration

Cause:
Existing node manager home directory does not exist or is not accessible.

Action:
Specify a valid directory or check permissions if it is not accessible.

CFGFWK-60929
Invalid port value.

Category:
Configuration

Cause:
The listen port value {3,number,#} of {1} "{2}" is out of range. It must be between 1 and 65535.

Action:
Enter a valid port value.

CFGFWK-60930
Failed to select template. Please run with logging turned on.

Category:
Configuration

Cause:
There may be issues with the template(s) and/or with the template location(s).

Action:
Fix template(s) and/or provide correct template location(s).

CFGFWK-60931
Failed to process database information.

Category:
Configuration

Cause:
Failed to process database information.

Action:
Fix db info in the template(s).

CFGFWK-60932
Invalid listen port.

Category:
Configuration

Cause:
Port number must be between 1 and 65535, and different from SSL listen port and Coherence port.

Action:
Fix the listen port.

CFGFWK-60933
Invalid ssl port.

Category:
Configuration

Cause:
Port number must be between 1 and 65535, and different from listen port and Coherence port.

Action:
Fix the ssl port.

CFGFWK-60934
Invalid coherence port.

Category:
Configuration

Cause:
Port number must be between 1 and 65535, and different from listen port and SSL listen port.

Action:
Fix the Coherence port.

CFGFWK-60935
Failed to select template.

Category:
Configuration

Cause:
Please see the log file {0} for details.

Action:
Fix template(s) and/or its location in the configuration file. Also check the validity of the configuration xml file.

CFGFWK-60950
Required template not found in new installation directory

Category:
Configuration

Cause:
A template that was required for the reconfiguration could not be found in the upgraded MiddleWare home: {0}

Action:
Refer to upgrade documentation for information about installation and product migration.

CFGFWK-60951
Failed to load reconfiguration template

Category:
Configuration

Cause:
The reconfiguration template {0} failed to load due to invalid meta-data

Action:
Correct the template.

CFGFWK-60952
Failed to load replacement template

Category:
Configuration

Cause:
Unable to load the template {0}

Action:
Correct the template

CFGFWK-60953
An application or library was not relocated to the new MW home.

Category:
Configuration

Cause:
An error in the reconfiguration templates resulted in the following deployments being left in the original MW home: {0}

Action:
Correct the reconfiguration templates

CFGFWK-60954
A reconfiguration template cannot be the replacement for another reconfiguration template

Category:
Configuration

Cause:
The reconfiguration template {0} specified another reconfiguration template {1} as its replacement. The replacement must be either an extension or domain template.

Action:
Correct the reconfiguration template

CFGFWK-60955
Unable to locate the WebLogic Server component.

Category:
Configuration

Cause:
The domain did not contain component references corresponding to known WebLogic Server components

Action:
None; the domain cannot be reconfigured

CFGFWK-60956
Unable to locate the certifiate.

Category:
Configuration

Cause:
The certificate does not exist at given location {0}.

Action:
Browse or provide the proper certificate location

CFGFWK-60957
Unable to locate the private key file.

Category:
Configuration

Cause:
The private key file does not exist at given location {0}.

Action:
Browse or provide the proper private key file location

CFGFWK-60958
The empty password is not allowed.

Category:
Configuration

Cause:
The password is not provided.

Action:
Provide the valid password.

CFGFWK-60959
Unable to locate the certifiate.

Category:
Configuration

Cause:
The certificate does not exist at given location {0}.

Action:
Browse or provide the proper certificate location

CFGFWK-60960
Unable to locate the jks file.

Category:
Configuration

Cause:
The jks file does not exist at given location {0}.

Action:
Browse or provide the proper jks file location

CFGFWK-60961
The password must be at least 8 alphanumeric characters with at least one number or special character.

Category:
Configuration

Cause:
The password is not valid.

Action:
Provide the valid password.

CFGFWK-60962
The empty password is not allowed.

Category:
Configuration

Cause:
The password is not provided.

Action:
Provide the valid password.

CFGFWK-60963
The password must be valid for this keystore.

Category:
Configuration

Cause:
The password is not valid for this keystore.

Action:
Provide the valid password for this keystore.

CFGFWK-60964
The alias name must be contained in this keystore.

Category:
Configuration

Cause:
The keystore does not contain the alias name.

Action:
Provide an alias name that is in this keystore.

CFGFWK-60965
The password must be valid for this alias name.

Category:
Configuration

Cause:
The password is not valid for this alias name.

Action:
Provide the valid password for this alias name.

CFGFWK-60966
The keystore information must be complete.

Category:
Configuration

Cause:
The keystore information is not complete.

Action:
Provide complete keystore information.

CFGFWK-60967
The keystore alias name should not contain duplicates.

Category:
Configuration

Cause:
The keystore alias names contains duplicates.

Action:
Provide provide different alias names.

CFGFWK-60970
Reconfigured domain had template dependency conflicts

Category:
Configuration

Cause:
Invalid reconfiguration templates left the domain in an invalid state.

Action:
Correct the reconfiguration templates

CFGFWK-60971
The domain is not reconfigurable.

Category:
Configuration

Cause:
The domain did not contain information necessary to determine how to reconfigure the domain.

Action:
Refer to the upgrade documentation on how to proceed.

CFGFWK-61000
Failed to create CAM instance.

Category:
Configuration

Cause:
An error occured while generating a CAM instance.

Action:
Check the log for more information.

CFGFWK-61001
Invalid system component schema with details

Category:
Configuration

Cause:
An error occurred while validating the schema for System Component. {0}

Action:
Set all the required properties for system component.

CFGFWK-61010
The entered Domain Frontend URL is invalid.

Category:
Configuration

Cause:
An error occured while validating the URL {0}

Action:
Please enter a valid URL.

CFGFWK-61011
The Domain Frontend URLs could not be set in ConfigMapping

Category:
Configuration

Cause:
The Frontend host were not set in Config Mapping.

Action:
Please check log for more information.

CFGFWK-61012
The Schema entered for Domain Frontend URL is invalid.

Category:
Configuration

Cause:
An error occured while validating the Schema for the URL {0}

Action:
Please enter a valid URL.

CFGFWK-61013
The entered Address for Domain Frontend URL is invalid.

Category:
Configuration

Cause:
An error occured while validating the Address for the URL {0}

Action:
Please enter a valid URL.

CFGFWK-61014
The entered Port for Domain Frontend URL is invalid.

Category:
Configuration

Cause:
An error occured while validating the Port for the URL {0}

Action:
Please enter a valid URL.

CFGFWK-61015
The url for the field cannot be null or empty

Category:
Configuration

Cause:
An error occured while validating the URL. The URL cannot be Null or empty.

Action:
Please enter an URL.

CFGFWK-61020
Frontend HTTP/HTTPS Port has been entered, but Frontend Host is missing.

Category:
Configuration

Cause:
Frontend Host is empty.

Action:
Enter a valid Frontend Host address.

CFGFWK-61021
Frontend Host has been entered, but Frontend HTTP/HTTPS Port is missing.

Category:
Configuration

Cause:
Frontend HTTP/HTTPS Port is empty.

Action:
Enter a valid Frontend HTTP/HTTPS Port.

CFGFWK-62002
Invalid Oracle home location

Category:
Configuration

Cause:
Given Oracle home ("{0}") does not exist.

Action:
Provide valid Oracle home.

CFGFWK-62003
Oracle home location is missing

Category:
Configuration

Cause:
Oracle home location is not specified.

Action:
Specify the Oracle home location.

CFGFWK-62004
Location is not a directory

Category:
Configuration

Cause:
The given location ("{0}") is not a directory.

Action:
Provide a valid location.

CFGFWK-62005
No template found in the given Oracle home.

Category:
Configuration

Cause:
The given location ("{0}") is not a valid Oracle home.

Action:
Provide a valid Oracle home.

CFGFWK-62006
Error occurred in templates retrieval

Category:
Configuration

Cause:
Error occurred: "{0}"

Action:
Check the log for more details.

CFGFWK-62007
No choice selected

Category:
Configuration

Cause:
No flow choice selected

Action:
Select a valid choice

CFGFWK-62008
Invalid value of "{0}" property.

Category:
Configuration

Cause:
Property "{0}" of {1} "{2}" is invalid. The name must not be null or empty and may not contain any ^ [^ * : , = ? % /] + $

Action:
Provide valid property value.

CFGFWK-62009
Invalid value of "{0}" property.

Category:
Configuration

Cause:
Property "{0}" of {1} is invalid. {0} must start with /

Action:
Provide valid property value.

CFGFWK-62010
Invalid value of "{0}" property.

Category:
Configuration

Cause:
Port values for "{2}" of {1} is invalid. Either Explicit Port or Port Offset must to be set to a non zero value or an unique URI Prefix must be specified.

Action:
Provide valid property value.

CFGFWK-62011
Invalid value of "{0}" property.

Category:
Configuration

Cause:
Port values for "{2}" of {1} is invalid. Cannot set both Explicit Port and Port Offset.

Action:
Provide valid property value.

CFGFWK-62012
Invalid server name prefix.

Category:
Configuration

Cause:
Server name prefix cannot be empty.

Action:
Provide server name prefix value.

CFGFWK-62013
Server template cannot be 'unspecified'.

Category:
Configuration

Cause:
Server template cannot be 'unspecified' if cluster is dynamic.

Action:
Choose a server template.

CFGFWK-62014
Same server template cannot be associated with different clusters.

Category:
Configuration

Cause:
Same server template cannot be associated with different clusters.

Action:
Choose a different server template.

CFGFWK-64001
Property value is not part of enumerated values.

Category:
Configuration

Cause:
According to the XML schema, the value for property {0} of {1} must be one of the following: {3}.

Action:
Use one of the valid values.

CFGFWK-64002
Invalid property value.

Category:
Configuration

Cause:
The value "{3}" for property "{0}" of {1} {2} did not pass XML schema validation: {4}.

Action:
Provide valid value.

CFGFWK-64009
The "{0}" property is missing.

Category:
Configuration

Cause:
"{0}" is empty. It must be set on the {1} objects. The name must not be null or empty.

Action:
Provide a name.

CFGFWK-64010
Invalid property value.

Category:
Configuration

Cause:
Property "{0}" of {1} "{2}" is invalid.

Action:
Provide valid property value.

CFGFWK-64012
Invalid property value.

Category:
Configuration

Cause:
Property "{0}" of {1} "{2}" is invalid. Space characters are not allowed.

Action:
Provide valid property value.

CFGFWK-64013
Internal representation conversion error.

Category:
Configuration

Cause:
The string cannot be converted.

Action:
Check the logs for more information.

CFGFWK-64014
The required property is missing.

Category:
Configuration

Cause:
Invalid property "{0}" of {1}: value "{2}" is invalid. The property value is required.

Action:
Provide property value.

CFGFWK-64015
Duplicated property.

Category:
Configuration

Cause:
Invalid property "{0}" of {1}: value "{2}" is invalid. The property value is duplicated.

Action:
Correct the property value.

CFGFWK-64016
Attempt to set disabled property.

Category:
Configuration

Cause:
The property "{0}" is disabled on type {1}.

Action:
Internal error. No user actions available.

CFGFWK-64017
Attempt to set unsupported property.

Category:
Configuration

Cause:
The property "{0}" is not supported on type {1}.

Action:
Internal error. No user actions available.

CFGFWK-64018
Mismatched password values.

Category:
Configuration

Cause:
The password value does not match the confirmation password.

Action:
Correct password values.

CFGFWK-64019
The "{0}" property is missing.

Category:
Configuration

Cause:
"{0}" is empty. It must be set on the {1} objects. The name must not be null or empty and should contain valid characters only.

Action:
Provide a name.

CFGFWK-64020
The file "{0}" does not exist or is not a file.

Category:
Configuration

Cause:
"{0}" does not exist or is not a file.

Action:
Provide a file name.

CFGFWK-64021
Fatal internal error.

Category:
Configuration

Cause:
An unexpected internal condition was detected: {0}. The wizard cannot continue.

Action:
Check the logs for more information.

CFGFWK-64022
Unspecified error.

Category:
Configuration

Cause:
One of the subsystems generated an error: {0}

Action:
Check error text for more information.

CFGFWK-64023
The file "{0}" does not have permission to read.

Category:
Configuration

Cause:
"{0}" does not have permission to read.

Action:
Provide a read permission.

CFGFWK-64024
The file "{0}" does not have permission to write.

Category:
Configuration

Cause:
"{0}" does not have permission to write.

Action:
Provide a write permission.

CFGFWK-64025
Maximum number of entries reached.

Category:
Configuration

Cause:
At most {0} entries can be created.

Action:
Operation aborted; no further action required.

CFGFWK-64026
Maximum number of entries reached.

Category:
Configuration

Cause:
At most 1 entry can be created.

Action:
Operation aborted; no further action required.

CFGFWK-64027
Minimum number of entries not reached.

Category:
Configuration

Cause:
At least {0} entries must be provided.

Action:
Operation aborted; no further action required.

CFGFWK-64028
Minimum number of entries not reached.

Category:
Configuration

Cause:
At least 1 entry must be provided.

Action:
Operation aborted; no further action required.

CFGFWK-64029
Can not remove entry.

Category:
Configuration

Cause:
Disabled entry may not be removed.

Action:
Removal aborted. No user actions available.

CFGFWK-64030
The target file must be specified.

Category:
Configuration

Cause:
The target file must be specified.

Action:
Provide a target file.

CFGFWK-64031
The service-id and service-type both are required for the service type "NEW".

Category:
Configuration

Cause:
The service-id and service-type both are required for the service type "NEW".

Action:
Provide a service-id and service-type.

CFGFWK-64032
The output-date-target element must be specified.

Category:
Configuration

Cause:
The output-date-target element must be specified.

Action:
Provide a output-date-target element.

CFGFWK-64033
The invalid input-data-src type specified.

Category:
Configuration

Cause:
The invalid input-data-src type specified.

Action:
Provide a valid input-data-src type.

CFGFWK-64034
The target xpath for a token bind or target-key for an xml bind is not applicable.

Category:
Configuration

Cause:
The target xpath for a token bind or target-key for an xml bind is not applicable.

Action:
Provide a target-key for a token bind or target-xpath for an xml bind.

CFGFWK-64035
Multiple assignment to target.

Category:
Configuration

Cause:
The {0} "{1}" could not be assigned to the target "{2}" since each target can have only one {0} assigned.

Action:
Change the assignment.

CFGFWK-64036
The invalid app-svc-name "{0}" is defined.

Category:
Configuration

Cause:
The invalid app-svc-name "{0}" is defined.

Action:
Provide a valid app-svc-name.

CFGFWK-64037
The invalid FEHost Address type "{0}" is defined.

Category:
Configuration

Cause:
The invalid FEHost Address type "{0}" is defined.

Action:
Provide a valid FEHost Address type.

CFGFWK-64038
The app-svc-name "{0}" must have target.

Category:
Configuration

Cause:
The app-svc-name "{0}" must have target.

Action:
Provide a valid target.

CFGFWK-64039
Unsupported property.

Category:
Configuration

Cause:
The property "{0}" is not supported on type {1}.

Action:
Internal error. No user actions available.

CFGFWK-64040
Invalid template location.

Category:
Configuration

Cause:
Specified template does not exist or is not a file: "{0}".

Action:
Provide a valid template location.

CFGFWK-64041
Invalid template.

Category:
Configuration

Cause:
Template "{0}" is not a valid jar file.

Action:
Provide a valid template location.

CFGFWK-64042
Invalid template.

Category:
Configuration

Cause:
Template "{0}" does not contain template-info.xml.

Action:
Provide a valid template location.

CFGFWK-64043
Invalid template.

Category:
Configuration

Cause:
template-info.xml could not be parsed: {0}

Action:
Provide a valid template location.

CFGFWK-64044
Invalid template.

Category:
Configuration

Cause:
XML schema validation failed for template-info.xml: {0}

Action:
Provide a valid template location.

CFGFWK-64045
Unable to save template-info.

Category:
Configuration

Cause:
Encountered error while saving template-info.xml: {0}

Action:
Check generated exception for details.

CFGFWK-64050
Invalid location

Category:
Configuration

Cause:
No template was selected

Action:
Select a valid template

CFGFWK-64051
Invalid location.

Category:
Configuration

Cause:
The selected location does not contain WebLogic domain.

Action:
Select a valid domain.

CFGFWK-64052
Invalid configuration

Category:
Configuration

Cause:
This is not a valid configuration! Correct the following error in config.xml: {0}

Action:
Correct config.xml

CFGFWK-64053
Domain loading error.

Category:
Configuration

Cause:
The Configuration Wizard encountered problems attempting to load the domain you selected: {0}.

Action:
Select a different domain.

CFGFWK-64054
Unsupported domain.

Category:
Configuration

Cause:
The domain in this directory is not a supported version.

Action:
Select a different domain.

CFGFWK-64055
Invalid template extension.

Category:
Configuration

Cause:
Template destination is not having a valid extension.

Action:
Correct the template destination extension to .jar.

CFGFWK-64056
Error adding templates.

Category:
Configuration

Cause:
The Configuration Wizard encountered problems attempting to add templates you selected: {0}.

Action:
Verify template integrity or select different templates.

CFGFWK-64058
Incompatible templates.

Category:
Configuration

Cause:
Some of the extension templates you have selected are incompatible with each other due to conflicting application and/or service names: {0}

Action:
Modify template selection.

CFGFWK-64059
Unsatisfied conditions.

Category:
Configuration

Cause:
The template you selected cannot be applied because the following conditions have not been satisfied: {0}

Action:
Select "Yes" to override these conditions (Not Recommended).

CFGFWK-64062
Invalid template.

Category:
Configuration

Cause:
Domain template "{0}" could not be loaded: {1}

Action:
Select a valid domain template

CFGFWK-64063
Missing config.xml in template

Category:
Configuration

Cause:
The config.xml is invalid or missing in the template selected

Action:
Select a valid template

CFGFWK-64064
No domain template in selection.

Category:
Configuration

Cause:
Selection must contain at least one domain template. Currently selected templates are defined as extension templates and do not express a dependency on a domain template.

Action:
Include domain template into your selection.

CFGFWK-64065
No templates added.

Category:
Configuration

Cause:
At least one template needs to be added to configuration.

Action:
Add a template.

CFGFWK-64066
Template location is missing.

Category:
Configuration

Cause:
Template location is not provided.

Action:
Specify template location.

CFGFWK-64067
Invalid template.

Category:
Configuration

Cause:
Only Oracle product templates from the Oracle Home already associated with this domain are eligible for selection.

Action:
Select a template associated with the current Oracle Home.

CFGFWK-64069
Missing template prerequisites.

Category:
Configuration

Cause:
The following prerequisites could not be satisfied: {0}

Action:
Verify that prerequisite templates are present or change your selection.

CFGFWK-64070
Template conflict.

Category:
Configuration

Cause:
The following templates are both prerequisites and conflicts for the current selection: {0}

Action:
Selection is reverted. No further actions required.

CFGFWK-64071
Template conflict.

Category:
Configuration

Cause:
The selection conflicts with templates already present in the domain: {0}

Action:
Selection is reverted. No further actions required.

CFGFWK-64072
Ambiguous prerequisite.

Category:
Configuration

Cause:
There are multiple matches for one of the prerequisites specified by a template. Resolve the ambiguity by preselecting one of the choices before attempting selection: {0}

Action:
Select the desired prerequisite.

CFGFWK-64073
Non-selectable template.

Category:
Configuration

Cause:
The template is not selectable in the current mode.

Action:
Selection is reverted. No further actions required.

CFGFWK-64074
Missing template.

Category:
Configuration

Cause:
The template is not available.

Action:
Selection is reverted. No further actions required.

CFGFWK-64075
Template is configured.

Category:
Configuration

Cause:
The template was previously configured.

Action:
Selection is reverted. No further actions required.

CFGFWK-64076
Template already selected.

Category:
Configuration

Cause:
The template is already selected.

Action:
Selection is reverted. No further actions required.

CFGFWK-64077
Template already unselected.

Category:
Configuration

Cause:
The template is already unselected.

Action:
Selection is reverted. No further actions required.

CFGFWK-64078
Template selection error.

Category:
Configuration

Cause:
Encountered error during selection operation: {0}

Action:
Selection is reverted. No further actions required.

CFGFWK-64079
Template conflict.

Category:
Configuration

Cause:
The selection requires templates which conflicts with the current domain: {0}

Action:
Selection is reverted. No further actions required.

CFGFWK-64080
Invalid template config-groups.

Category:
Configuration

Cause:
The Template {0} with version {1} and template location {2} contains config-groups with app-svcs names {3} which are not present in the configuration.

Action:
remove invalid app-svcs names from config-groups.

CFGFWK-64085
Directory not selected.

Category:
Configuration

Cause:
A directory was not set.

Action:
Select a valid directory.

CFGFWK-64086
'Extension Template' as a source not allowed.

Category:
Configuration

Cause:
Selection of an 'Extension Template' as source for 'Domain Template' creation is not supported.

Action:
Select a valid source.

CFGFWK-64087
Invalid source type.

Category:
Configuration

Cause:
Selection of an Oracle product 'Extension Template' as a source is not allowed.

Action:
Select a valid source.

CFGFWK-64100
Invalid help topic.

Category:
Configuration

Cause:
No such help topic exists.

Action:
Provide valid help topic.

CFGFWK-64101
Help is not configured

Category:
Configuration

Cause:
No Help configuration found.

Action:
Configure help.

CFGFWK-64102
Invalid help type.

Category:
Configuration

Cause:
Help type not supported.

Action:
Provide the valid help type.

CFGFWK-64103
Failed to load help.

Category:
Configuration

Cause:
Errors occurred while loading Help.

Action:
Check the logs for more information.

CFGFWK-64104
Low console width.

Category:
Configuration

Cause:
Value of console width is too low!

Action:
Increase the console width.

CFGFWK-64200
No common database driver.

Category:
Configuration

Cause:
The selected data sources do not share any common database drivers. The wizard will deselect data sources to allow selection of compatible drivers.

Action:
No action required.

CFGFWK-64201
No common database driver.

Category:
Configuration

Cause:
The selected component schemas do not share any common database drivers. The wizard will deselect component schemas to allow selection of compatible drivers.

Action:
No action required.

CFGFWK-64204
Validation errors.

Category:
Configuration

Cause:
Some more validation errors occurred.

Action:
Correct validation errors.

CFGFWK-64205
Unspecified property.

Category:
Configuration

Cause:
The {0} must be specified.

Action:
Specify the property.

CFGFWK-64206
Unspecified properties.

Category:
Configuration

Cause:
The following must be specified: {0}

Action:
Provide missing properties.

CFGFWK-64207
Mismatched passwords.

Category:
Configuration

Cause:
The {0} and {1} do not match.

Action:
Correct the password.

CFGFWK-64208
Invalid value.

Category:
Configuration

Cause:
The {0} must be an integer.

Action:
Provide integer value.

CFGFWK-64209
Test Canceled!

Category:
Configuration

Cause:
You have cancelled the connection test.

Action:
No further action required.

CFGFWK-64210
Test Failed!

Category:
Configuration

Cause:
JDBC connection test failed.

Action:
Check logs for more information.

CFGFWK-64211
Test Failed!

Category:
Configuration

Cause:
Error getting connection information!

Action:
Provide connection details.

CFGFWK-64212
No rows returned.

Category:
Configuration

Cause:
A connection was established to the database but no rows were returned from the test SQL statement.

Action:
Check logs for more information.

CFGFWK-64213
Test Successful!

Category:
Configuration

Cause:
JDBC connection test was successful.

Action:
No action required.

CFGFWK-64215
There are no data sources selected.

Category:
Configuration

Cause:
Detected that there are no data sources selected.

Action:
Select the data sources that you want to test.

CFGFWK-64216
Data source {0} connection test failed.

Category:
Configuration

Cause:
Error message: {0}

Action:
Go to previous panels to fix the problem and test it again.

CFGFWK-64217
JDBC data source validations failed.

Category:
Configuration

Cause:
Error message: {0}

Action:
Go to previous panels to fix the problem and test it again.

CFGFWK-64218
Server configuration validations failed.

Category:
Configuration

Cause:
For instance {0}, valid input value for {1} must be specified,

Action:
Enter the required values.

CFGFWK-64219
Failed to bind the schema component data

Category:
Configuration

Cause:
Error message: {0}.

Action:
Enter the correct database connection parameters.

CFGFWK-64220
CopyFileDefinition validations failed.

Category:
Configuration

Cause:
The duplicate copy file definition name across multiple templates : {0}.

Action:
Each copy file definition must be defined with an unique name.

CFGFWK-64221
DeleteFileDefinition validations failed.

Category:
Configuration

Cause:
The duplicate delete file definition name across multiple templates : {0}.

Action:
Each delete file definition must be defined with an unique name.

CFGFWK-64222
CopyFileDefinition source exists validations failed.

Category:
Configuration

Cause:
The source location does not exist for the copy definition.

Action:
Correct the copy definition in the template to refer to a valid source location.

CFGFWK-64253
Error occurred in "{0}" phase initialization

Category:
Configuration

Cause:
Encountered error: {1}

Action:
Check log for more detail.

CFGFWK-64254
Error occurred in "{0}" phase execution

Category:
Configuration

Cause:
Encountered error: {1}

Action:
Check log for more detail.

CFGFWK-64255
Error occurred in parsing the configuration file: "{0}".

Category:
Configuration

Cause:
Encountered error: {1}

Action:
Check log for more detail.

CFGFWK-64256
Invalid Template location.

Category:
Configuration

Cause:
Template generation location is not set.

Action:
Check log for more detail.

CFGFWK-64257
Failed to delete old template.

Category:
Configuration

Cause:
Unable to delete existing template "{0}" file.

Action:
Check log for more detail.

CFGFWK-64258
Unable to create template directory.

Category:
Configuration

Cause:
Failed to create template "{0}" directory.

Action:
Check log for more detail.

CFGFWK-64261
Invalid Domain location.

Category:
Configuration

Cause:
Domain generation location was not set.

Action:
Check log for more detail.

CFGFWK-64262
Unable to create domain directory:

Category:
Configuration

Cause:
Unable to create domain directory: {0}

Action:
Check log for more detail.

CFGFWK-64263
Invalid Applications location.

Category:
Configuration

Cause:
Applications location not set.

Action:
Check log for more detail.

CFGFWK-64264
Unable to create applications directory.

Category:
Configuration

Cause:
Unable to create applications directory: {0}

Action:
Check log for more detail.

CFGFWK-64265
Invalid Scratch location.

Category:
Configuration

Cause:
Scratch location was not set.

Action:
Check log for more detail.

CFGFWK-64266
Unable to create scratch directory.

Category:
Configuration

Cause:
Unable to create scratch directory: {0}

Action:
Check log for more detail.

CFGFWK-64267
Error creating JarHelper

Category:
Configuration

Cause:
Encountered error: {0}

Action:
Check log for more detail.

CFGFWK-64268
Failed to create backup file

Category:
Configuration

Cause:
Unable to create backup of existing file: {0}

Action:
Check log for more detail.

CFGFWK-64272
Domain directory did not exist.

Category:
Configuration

Cause:
Domain directory "{0}" not found.

Action:
Check log for more detail.

CFGFWK-64273
Domain directory not set.

Category:
Configuration

Cause:
Missing Domain directory location.

Action:
Check log for more detail.

CFGFWK-64276
Reconfiguration Failed.

Category:
Configuration

Cause:
Failed to process macro rules error during reconfiguration!

Action:
Check log for more detail.

6
CHGHOST-20200 to CHGHOST-20219

CHGHOST-20200
The argument is invalid.

Category:
CHGHOST Configuration

Cause:
The argument {0} was not supported by chghost script.

Action:
Provide a valid argument. Use the "-help" option for more information about chghost script arguments.

CHGHOST-20201
The value for the argument is missing.

Category:
CHGHOST Configuration

Cause:
The argument {0} was provided, but its value was not provided.

Action:
Provide the corresponding value.

CHGHOST-20202
Log level is invalid

Category:
CHGHOST Configuration

Cause:
Invalid log level {0}. It was set via {1} for system property {2}.

Action:
Set a valid log level. Supported log levels are {0}.

CHGHOST-20203
The input validation failed for argument walletDir.

Category:
CHGHOST Configuration

Cause:
The wallet directory was not provided.

Action:
Make sure that the correct values are provided.

CHGHOST-20204
The database connection failed for the datasource.

Category:
CHGHOST Configuration

Cause:
Possible causes of failure for the datasource:{0} 1. Datasource {0} is not correct. 2. One or more connection parameters in DB url {1} are not proper.

Action:
Make sure that the database host is correct and database is cloned properly.

CHGHOST-20205
The database url is empty.

Category:
CHGHOST Configuration

Cause:
Possible causes of failure for the target DB_HOST : {0} 1. Datasource {1} is not correct. 2. Schema or User {2} is not proper.

Action:
Make sure that the database host is correct and database is cloned properly.

CHGHOST-20206
The input validation failed for argument chgHostInputFile.

Category:
CHGHOST Configuration

Cause:
File did not exist.

Action:
Make sure that the correct values are provided.

CHGHOST-20207
Host mappling entries are missing in chghost input File.

Category:
CHGHOST Configuration

Cause:
Both SERVER_HOST and DB_HOST entires were missing

Action:
Provide value for host mapping in chghost input File.

CHGHOST-20208
Domain home was invalid.

Category:
CHGHOST Configuration

Cause:
Provided domain home {0} was different from the domain home {1} , found from its internal configuration files.

Action:
Provide valid Domain home.

CHGHOST-20209
Java Home associated with domain home was invalid.

Category:
CHGHOST Configuration

Cause:
There were two possible causes for invalid java home {0} : 1. The directory did not exist. 2. The directory did not have correct binaries.

Action:
Make sure that the Java Home is valid.

CHGHOST-20210
Oracle Home did not have supported binaries.

Category:
CHGHOST Configuration

Cause:
The root causes were :{1}.

Action:
Make sure that the Oracle Home has correct binaries.

CHGHOST-20211
Oracle Home associated with domain home was invalid.

Category:
CHGHOST Configuration

Cause:
There were two possible causes for invalid Oracle home {0} : 1. The directory did not exist. 2. The director did not have correct binaries.

Action:
Make sure that the Oracle Home is valid.

CHGHOST-20212
Invalid wallet directory.

Category:
CHGHOST Configuration

Cause:
There are three possible causes for an invalid wallet directory {0}. 1. It was not a directory. 2. The directory was empty. 3. The directory did not have valid .sso file.

Action:
Provide a valid wallet directory.

CHGHOST-20213
The system temporary directory is inaccessible.

Category:
CHGHOST Configuration

Cause:
The system temporary directory {0} did not have write permission.

Action:
Make sure that system temporary directory has write permission.

CHGHOST-20214
The domain home validation failed.

Category:
CHGHOST Configuration

Cause:
The following file {0} did not exist under domain home.

Action:
Provide a valid domain location.

CHGHOST-20215
Invalid domain home location.

Category:
CHGHOST Configuration

Cause:
Path {0} was not absolute or an empty directory.

Action:
Provide a valid absolute path.

CHGHOST-20216
Invalid domain home location.

Category:
CHGHOST Configuration

Cause:
Path {0} was not readable.

Action:
Provide a valid absolute path.

CHGHOST-20217
Invalid server host.

Category:
CHGHOST Configuration

Cause:
Server host {0} was not valid.

Action:
Provide a valid server host.

CHGHOST-20218
Server ports validation failed.

Category:
CHGHOST Configuration

Cause:
The port {0} was used for multiple servers.

Action:
Provide different free ports for servers.

CHGHOST-20219
Server port validation failed.

Category:
CHGHOST Configuration

Cause:
Specified port {0} for server {1} was not free.

Action:
Provide valid free port.

7

DVT-02012 to DVT-26021

DVT-02012
Column {0} exceeds boundary {1}.

Category:
Programmatic

Cause:
The specified column number was greater than the total number of columns.

Action:
Get the total number of columns, by calling the getColumnCount method of the graph or of the column header in the pivot table. Then specify a column that does not exceed the total number of columns.

DVT-02013
Row {0} exceeds boundary {1}.

Category:
Programmatic

Cause:
The specified row number was greater than the total number of rows.

Action:
Get the total number of rows, by calling the getRowCount method of the graph or of the column header in the pivot table. Then specify a row that does not exceed the total number of rows.

DVT-02015
Slice {0} exceeds boundary {1}.

Category:
Programmatic

Cause:
The specified slice number was greater than the total number of slices.

Action:
Specify a slice that does not exceed the total number of slices.

DVT-02016
Layer {0} exceeds boundary {1}.

Category:
Programmatic

Cause:
The specified layer was greater than the total number of layers that are available on the given edge.

Action:
Specify a layer that does not exceed the total number of layers.

DVT-02017
Series {0} exceeds boundary {1}.

Category:
Programmatic

Cause:
The specified series was greater than the total series that is available in the graph.

Action:
Specify a zero-based series index that does not exceed the total series. The Graph.getDisplaySeries method should provide the number of series that are displayed in the graph. Or, if Graph.isDataRowShownAsASeries returns true, then Graph.getRowCount returns the number of series that can be displayed. If Graph.isDataRowShownAsASeries returns false, then Graph.getColumnCount returns the total number of series that can be displayed.

DVT-02018
Edge {0} exceeds boundary {1}.

Category:
Programmatic

Cause:
The specified edge was greater than the total number of edges that are available on the given edge. Valid edges for methods that require an edge are: DataDirector.COLUMN_EDGE, DataDirector.ROW_EDGE, and DataDirector.PAGE_EDGE.

Action:
Specify a valid edge constant.

DVT-02019
Current DataSource does not support required type: {0}.{1}.

Category:
Programmatic

Cause:
The DataSource did not support the required type of data in its DataMap. For example, the view requested DataMap.DATA_GROUPSORT information, and the DataSource that the view uses did not supply group sort information.

Action:
Request support for the required data types in the DataSource, or use a different DataSource.

DVT-02020
DTD file cannot be found.

Category:
Programmatic

Cause:
The specified DTD could not be found. The XML parser needed the DTD in order to validate XML files.

Action:
Ensure that the specified DTD file exists, or disable XML validation. DTDs for Data Visualization components are in their respective packages. To turn off validation, call Dataview.setXMLValidated(false);.

DVT-03000
No Mergeable object is provided.

Category:
Programmatic

Cause:
No default Mergeable object was provided to resolve rules.

Action:
Provide at least one default Mergeable object, so that rules can be resolved. For more information about Mergeable objects, see the Javadoc for the oracle.dss.rules.Mergeable interface.

DVT-03001
attempt to call merge(Mergeable) on an incompatible Mergeable class

Category:
Programmatic

Cause:
An attempt was made to merge incompatible Mergeable classes. Only Mergeable objects of the same class can be merged. For example, ViewStyle objects can be merged, but a ViewStyle cannot be merged with a ViewFormat.

Action:
Merge two classes that are compatible. For more information, see the Javadoc for the oracle.dss.rules.RuleBundle class.

DVT-06000
unexpected data error from Pivot Table data model

Category:
Data

Cause:
An unexpected exception was thrown by the Pivot Table's data model.

Action:
Log a bug against the application. Verify that the Pivot Table's data model is configured properly.

DVT-06001
no Converter for data type {0} during Pivot Table text formatting

Category:
Configuration

Cause:
The application could not create a Converter for a specific data type. The most likely reason was that a Converter was not registered for that data type.

Action:
Log a bug against the application. Verify that the application can create a default Converter for all data types rendered by the Pivot Table.

DVT-07001
cannot create Graph image

Category:
Programmatic

Cause:
Under heavy loads, there was not enough memory to create the BufferedImage, or the Graphics instance from the BufferedImage. Therefore, the generated image file is empty.

Action:
Reduce the memory load; for example, reduce the image size or allocate more memory to the JVM.

DVT-08000
unexpected data error from Data Model

Category:
Data

Cause:
An invalid operation was performed by Data Model.

Action:
Log a bug against the application. Verify that the Data model is configured properly.

DVT-22004
cannot create Gauge image

Category:
Programmatic

Cause:
Under heavy loads, there was not enough memory to create the BufferedImage, or the Graphics instance from the BufferedImage. Therefore, the generated image file is empty.

Action:
Reduce the memory load; for example, reduce the image size or allocate more memory to the JVM.

DVT-23000
End date cannot be earlier than start date.

Category:
Programmatic

Cause:
The end date specified for the Gantt chart was earlier than the specified start date.

Action:
Specify a correct start date and end date for the Gantt chart.

DVT-23001
The time unit in the major axis must be greater than the time unit in the minor axis.

Category:
Programmatic

Cause:
The time unit specified in the major axis was not greater than the time unit specified in the minor axis. For example, if "days" was specified as the time unit for the minor axis, then the time unit specified in the major time axis must be greater than "days", such as "months", and not anything less, such as "hours".

Action:
Ensure that the time unit in the major axis is greater than the time unit in the minor axis.

DVT-23002
An invalid time scale is specified.

Category:
Programmatic

Cause:
The specified time scale in the major or minor axis was not recognized.

Action:
Specify a valid time scale for the axis.

DVT-23003
End date of a task cannot be earlier than its start date. Start date: {0}, End date: {1}

Category:
Data

Cause:
The end date specified for the task was earlier than its start date.

Action:
Check the data to ensure that the start date and end date are loaded correctly.

DVT-23004
No tooltip keys or labels are specified.

Category:
Programmatic

Cause:
No tooltip keys or labels were specified in the Gantt tag.

Action:
Specify keys and labels for the tooltip to ensure that the tooltip is not empty.

DVT-23005
No legend keys or labels are specified.

Category:
Programmatic

Cause:
No legend keys or labels were specified in the Gantt tag.

Action:
Specify keys and labels for the legend to ensure that the legend is not empty.

DVT-23006
The number of tooltip keys does not match the number of tooltip labels.

Category:
Programmatic

Cause:
The number of tooltip keys did not match the number of tooltip labels specified in the Gantt tag.

Action:
Ensure that the number of tooltip keys specified in the Gantt tag (tooltipKeys attribute) matches the tooltip labels specified in the Gantt tag (tooltipLabels attribute).

DVT-23007
The number of legend keys does not match the number of legend labels.

Category:
Programmatic

Cause:
The number of legend keys did not match the number of legend labels specified in the Gantt tag.

Action:
Ensure that the number of legend keys specified in the Gantt tag (legendKeys attribute) matches the legend labels specified in the Gantt tag (legendKeyLabels attribute).

DVT-23008
The start date of the task is out of range. Value: {0}

Category:
Data

Cause:
The start and end date of a task was outside of the time range specified for the Gantt chart.

Action:
No action necessary, if it is okay not to show the task. Otherwise, verify data is correct or specify a wider time range for the Gantt chart (using the startTime and endTime attributes)

DVT-23009
cannot find format for type {0}; skipping task: {1}

Category:
Programmatic

Cause:
No format for type {0} was registered.

Action:
Register a TaskbarFormat with the TaskbarFormatManager for the type indicated.

DVT-23010
The specified day of the week is invalid. Value: {0}

Category:
Programmatic

Cause:
The day of the week specified was not recognized.

Action:
Specify a value for the day of the week that is one of these seven constants from the java.util.Calendar class: Calendar.SUNDAY, Calendar.MONDAY, Calendar.TUESDAY, Calendar.WEDNESDAY, Calendar.THURSDAY, Calendar.FRIDAY, Calendar.SATURDAY.

DVT-23011
The value specified for alignment is invalid. Task ID: {0}

Category:
Programmatic

Cause:
The alignment value specified for the label or icon was invalid.

Action:
Specify a value for alignment that is one of these three constants from the oracle.adf.view.faces.bi.component.gantt.GanttConstants class: GanttConstants.LEFT, GanttConstants.RIGHT, GanttConstants.INSIDE.

DVT-23012
GanttDropTarget can only be attached to a Gantt component.

Category:
Programmatic

Cause:
The GanttDropTarget tag was added as a child of a non-Gantt component.

Action:
Ensure that the GanttDropTarget tag is a child tag of either a Project Gantt or Scheduling Gantt component.

DVT-23013
The start date of a task is null.

Category:
Data

Cause:
The start date of a task was null.

Action:
Check the data to ensure that the start date is not null.

DVT-23014
The task ID is null.

Category:
Data

Cause:
The task ID or split task ID was null.

Action:
Check the data to ensure that the task ID or split task ID is not null.

DVT-23015
The next date cannot be earlier than the previous date.

Category:
Programmatic

Cause:
The next date returned by custom timescale was earlier than the previous date.

Action:
Specify a correct next date.

DVT-23016
The value supplied for the attribute is returning a wrong type.

Category:
Data

Cause:
The value supplied for the attribute is returning a wrong type.

Action:
Chech the attribute and modify to return correct type.

DVT-23017
The taskID is not unique in the resource. resourceID: {0}, taskID: {1}

Category:
Data

Cause:
The taskID is not unique in the resource.

Action:
Check the data to ensure that the task ID is unique.

DVT-26000
unable to find connection in {0}

Category:
Programmatic

Cause:
Either the map configuration was not valid, or connection information was missing.

Action:
Check the map configuration file.

DVT-26001
theme \"{0}\" cannot be displayed: missing value property

Category:
Programmatic

Cause:
The value attribute of the theme was null.

Action:
Check the value attribute of the theme.

DVT-26002
theme \"{0}\" cannot be displayed: invalid row key at row {1}

Category:
Programmatic

Cause:
The specified row either did not have a row key, or the row id in the row key was null.

Action:
Check the key and row id for the specified row.

DVT-26004
theme \"{0}\" cannot be displayed: row {1} with id={2} does not have a data value

Category:
Programmatic

Cause:
The specified row did not have a data value.

Action:
Check the data value for the specified row.

DVT-26005
theme \"{0}\" cannot be displayed: row {1} with id={2} does not have a location value

Category:
Programmatic

Cause:
The specified row did not have a location value.

Action:
Check the location value for the specified row.

DVT-26006
Labels for one or more rows of theme \"{0}\" are missing.

Category:
Programmatic

Cause:
Some rows in the theme did not have a location label.

Action:
Check the location labels in the theme.

DVT-26008
Theme \"{0}\" does not have any data.

Category:
Data

Cause:
The specified theme did not return any rows.

Action:
Check whether the specified theme is correctly returning no data.

DVT-26009
unable to geocode data at row {0} of theme \"{1}\": {2}

Category:
Data

Cause:
The specified data could not be geocoded.

Action:
Change the location value for the specified row.

DVT-26010
The mouse click behavior of {0} is to render a popup, but there is no popup facet in the map.

Category:
Data

Cause:
The map had no popup facet, but the leftClickBehavior property was specified to render a popup.

Action:
Check whether the mouse click behavior is correct.

DVT-26011
The right-click behavior of {0} is to render a popup, but there is no popup facet in the map.

Category:
Data

Cause:
The map had no popup facet, but the rightClickBehavior property was specified to render a popup.

Action:
Check whether the right-click behavior is correct.

DVT-26012
The number of labels specified in legendLabels does not match the number of buckets. Legend labels: {0}, Buckets: {1}

Category:
Data

Cause:
The number of legend labels and buckets did not match.

Action:
Check the number of legend labels.

DVT-26013
unable to geocode the theme data: no Geocoder URL specified in {0}

Category:
Programmatic

Cause:
Either the map configuration was not valid, or connection information for the Geocoder was missing.

Action:
Check the map configuration file.

DVT-26014
unable to show all theme data for theme \"{0}\": multiple data values for {1} are specified but only the first data value is shown

Category:
Programmatic

Cause:
Duplicate location data values were found.

Action:
Check the data for duplicate location values.

DVT-26015
theme \"{0}\" cannot be displayed: no longitude data at row {1}

Category:
Programmatic

Cause:
The specified row did not have a longitude value.

Action:
Check the longitude for the specified row.

DVT-26016
theme {0} cannot be displayed: no latitude data at row {1}

Category:
Programmatic

Cause:
The specified row did not have a latitude value.

Action:
Check the latitude for the specified row.

DVT-26017
unable to connect to MapViewer at {0}

Category:
Programmatic

Cause:
A MapViewer server was not found at the specified map URL.

Action:
Check whether the connection URL is correct and the MapViewer servlet can accept new requests.

DVT-26018
unable to connect to Geocoder at {0}

Category:
Programmatic

Cause:
The component was unable to connect to the Geocoder at the specified URL.

Action:
Check whether the connection URL is correct and the Geocoder can accept new requests.

DVT-26019
unable to find a map of id {0} for mapToolbar {1}

Category:
Programmatic

Cause:
The mapId attribute of the specified mapToolbar was not correct.

Action:
Check the mapId attribute of the specified mapToolbar.

DVT-26020
A map tag cannot have more than one mapOverview tag.

Category:
Programmatic

Cause:
There were more than one mapOverview tags in the map tag.

Action:
Remove any extra mapOverview tags.

DVT-26021
A map tag cannot have more than one mapLegend tag.

Category:
Programmatic

Cause:
There were more than one mapLegend tags in the map tag.

Action:
Remove any extra mapLegend tags.

8

EM-00251 to EM-02674

EM-00251
No connection to the WebLogic managed server {0}.

Category:
Enterprise Manager

Cause:
The WebLogic managed server was down.

Action:
Verify that the managed server is up and running.

EM-00252
Error in accessing proxy MBean for this system component in WebLogic managed server {0}

Category:
Enterprise Manager

Cause:
Component was down

Action:
Start the component, or verify that the component has been deployed on the managed server.

EM-00268
Error in querying ports configuration for system component {0}

Category:
Enterprise Manager

Cause:
Component was down

Action:
Start the component.

EM-00301
Error in fetching data from target application.

Category:
Enterprise Manager

Cause:
Target application is down.

Action:
Ensure target application is running.

EM-00302
Error fetching data from target server in the Oracle WebLogic Server domain.

Category:
Enterprise Manager

Cause:
The target WebLogic server is down.

Action:
Make sure the target server is up and running.

EM-00303
Error in discovering web service endpoints for target application.

Category:
Enterprise Manager

Cause:
Target application is down.

Action:
Ensure target application is running.

EM-00351
Unable to connect to Oracle WSM Policy Manager.

Category:
Enterprise Manager

Cause:
The Oracle WSM Policy Manager was down or not accessible.

Action:
Make sure Oracle WSM Policy Manager (wsm-pm application) is up and accessible. Also, ensure you have right roles to access the Service.

EM-00426
Unable to save changes to registered service

Category:
Enterprise Manager

Cause:
The service repository is unavailable.

Action:
Ensure that the service repository is up and running.

EM-00428
Unable to delete registered service

Category:
Enterprise Manager

Cause:
The service is no longer valid.

Action:
Ensure that the service is valid and is registered. Make sure the endpoint and WSDL for the service are accessible.

EM-00430
Unable to register service due to duplicate service name

Category:
Enterprise Manager

Cause:
The service name is already registered.

Action:
Ensure that the service name is unique.

EM-00432
Invalid WSIL URL

Category:
Enterprise Manager

Cause:
The WSIL URL is invalid. The URL is unreachable or doesn't contain a valid WSIL.

Action:
Ensure that the WSIL URL is valid and available.

EM-00434
Invalid WSIL File

Category:
Enterprise Manager

Cause:
The WSIL file is invalid. The file is not a valid WSIL document.

Action:
Ensure that the uploaded file is a valid WSIL document.

EM-00440
Service repository operation failed

Category:
Enterprise Manager

Cause:
Service repository is unavailable.

Action:
Ensure that the service repository is up and running.

EM-00451
Failed to access WSDL

Category:
Enterprise Manager

Cause:
Invalid WSDL location or WSDL is not accessible

Action:
Make sure you provide a valid WSDL location. If the location is valid, make sure it is accessible. Also, make sure you have proper privileges to access the WSDL with username and password.

EM-00452
Failed to parse WSDL file

Category:
Enterprise Manager

Cause:
Invalid WSDL content

Action:
Ensure that the WSDL is syntactically and semantically correct.

EM-00453
Failed to invoke operation

Category:
Enterprise Manager

Cause:
Invalid input arguments

Action:
Make sure you provide the required input argument values, and that the values are the proper type (for example, integer, string, and so on).

EM-00454
Failed to invoke operation

Category:
Enterprise Manager

Cause:
Unable to read SOAP action for selected operation

Action:
Make sure right SOAP Action value is set.

EM-00455
Failed to change view from 'XML View' to 'Tree View'

Category:
Enterprise Manager

Cause:
Invalid payload contents in XML format

Action:
Make sure you provide a valid payload to parse and check if any required tag is missing or broken.

EM-00456
Failed to change view from 'XML View' to 'Tree View'

Category:
Enterprise Manager

Cause:
Invalid input argument

Action:
Make sure you provide the required input argument values, and that the values are the proper type (for example, integer, string, and so on).

EM-00457
Failed to load key aliases from the keystore

Category:
Enterprise Manager

Cause:
Invalid keystore information

Action:
Make sure you provide a valid keystore location and password.

EM-00458
Failed to get compatible client policies from the WSDL

Category:
Enterprise Manager

Cause:
The WSDL is not accessible or you do not have the privilege to get policies.

Action:
Make sure you have the privilege to get the client policies.

EM-00459
Failed to update the URL with the server IP address.

Category:
Enterprise Manager

Cause:
The IP address of the server is not available due to database connection failure or missing target information.

Action:
Make sure you have the target discovered successfully with the server IP address.

EM-00501
TopLink Sessions were not found

Category:
Enterprise Manager

Cause:
TopLink MBeans were not found

Action:
Ensure that the application has been accessed to register the MBeans. Make sure that "-Declipselink.register.dev.mbean=true" and "-Declipselink.register.run.mbean=true" are part of $JAVA_OPTIONS

EM-00601
Error in getting WSDL for Web service client.

Category:
Enterprise Manager

Cause:
Target web service application is down.

Action:
Ensure target web service application is running.

EM-00602
Error in attaching/detaching policies.

Category:
Enterprise Manager

Cause:
Target application or Oracle WSM Policy Manager is down.

Action:
Ensure target application and Oracle WSM Policy Manager is running.

EM-00603
Error in getting policy subject from target application.

Category:
Enterprise Manager

Cause:
Target web service application is down.

Action:
Ensure target Web service application is running.

EM-01052
Error in querying OPSS application policy MBean object name.

Category:
Enterprise Manager

Cause:
The WebLogic managed server was down.

Action:
Verify that the managed server is up and running.

EM-01053
Application stripe entry {0} does not exist in policy store.

Category:
Enterprise Manager

Cause:
Application stripe ID used to access policies from policy store did not have any data.

Action:
Check the application stripe ID data provided in configuring Fusion MiddleWare control application deployment wizard security task.

EM-01055
Error in querying OPSS system policy MBean object name.

Category:
Enterprise Manager

Cause:
The WebLogic managed server was down.

Action:
Verify that the managed server is up and running.

EM-01061
Error in querying OPSS credential store MBean object name.

Category:
Enterprise Manager

Cause:
The WebLogic managed server was down.

Action:
Verify that the managed server is up and running.

EM-01321
Cannot obtain application information

Category:
Enterprise Manager

Cause:
The application is not active

Action:
Make sure that the application is active or running

EM-01322
Cannot obtain MDS information for selected application

Category:
Enterprise Manager

Cause:
MDS is not properly configured for the application

Action:
Make sure that MDS config mbean is accessible on the mbean server. If it is not, verify that appropriate MDS configuration file (web.xml) contains ADFConfigRuntimeLifeCycleCallBack listener to register MDS config mbean and MDS is configured properly in adf-config.xml.

EM-01323
Error while performing MDS runtime (import, export or purge) operation

Category:
Enterprise Manager

Cause:
MDS runtime mbean is not found on runtime mbean server

Action:
Make sure that the MDS runtime mbean is accessible on runtime mbean server. If it is not, verify that appropriate MDS configuration file (weblogic-application.xml) contains WLLifecycleListener listener to register MDS runtime mbean.

EM-01324
Error while retrieving data from page cache

Category:
Enterprise Manager

Cause:
JavaBean stored in the session has expired or was destroyed

Action:
Start a fresh session by logging into EM again.

EM-01325
Cannot obtain MDS target repository information

Category:
Enterprise Manager

Cause:
MDS target repository is not configured

Action:
Verify the MDS configuration by checking the contents of the configuration files (for example, adf-config.xml and mds-config.xml).

EM-02006
Error retrieving Configuration MBeans for ADFConnectionMBeans {0}.

Category:
Enterprise Manager

Cause:
The ADF Connection and Configuration MBean is not available or accessible.

Action:
Configuration options currently unavailable. The application might be down, did not start properly, or is incorrectly packaged. Check the log files for further details.

EM-02056
Error getting DAD MBean.

Category:
Enterprise Manager

Cause:
The DAD MBean is not available or accessible.

Action:
Configuration options currently unavailable. The application might be down, did not start-up properly, or is incorrectly packaged. Check the log files for further detail.

EM-02057
Error getting Cache MBean Object Name.

Category:
Enterprise Manager

Cause:
The Cache MBean is not available or accessible.

Action:
Configuration options currently unavailable. The application might be down, did not start-up properly, or is incorrectly packaged. Check the log files for further detail.

EM-02058
Error getting Middle Tier MBean Object Name.

Category:
Enterprise Manager

Cause:
The Middle Tier MBean is not available or accessible.

Action:
Configuration options currently unavailable. The application might be down, did not start-up properly, or is incorrectly packaged. Check the log files for further detail.

EM-02063
Error getting Portal site URL.

Category:
Enterprise Manager

Cause:
Wiring MBean Could not connect to the Portal repository.

Action:
The Portal Database maybe down or the Portal DAD has incorrect username, password or connect string information. Check the log files for further detail.

EM-02201
Error connecting to the Domain Runtime MBean Server.

Category:
Enterprise Manager

Cause:
The admin server is not working properly.

Action:
Ensure the target admin server is running properly.

EM-02202
Error getting the list of folders from the credential store.

Category:
Enterprise Manager

Cause:
There are issues with the JPS credential store MBean.

Action:
Ensure the JPS credential store MBean is registered and working properly through the System MBean Browser.

EM-02203
Error obtaining the UMS server information.

Category:
Enterprise Manager

Cause:
The UMS server is down, or not started properly, or not deployed on the target.

Action:
Ensure the UMS server is running properly.

EM-02251
Error connecting to Forms Config MBeans

Category:
Enterprise Manager

Cause:
The managed server that hosts the Forms application was down, or the Forms application was down or not deployed on this server.

Action:
Depending on the specific cause, start the managed server if it is down, start the Forms application if it is down, or deploy the Forms application on this domain if haven't been deployed already.

EM-02652
error while initializing data for the BI Instance {0}

Category:
Enterprise Manager

Cause:
The server for Fusion Middleware Control failed to correctly communicate with the server for the BI Instance.

Action:
Ensure that the server for the BI Instance is running.

EM-02653
error while initializing data for the BI Instance {0}

Category:
Enterprise Manager

Cause:
The server for Fusion Middleware Control failed to correctly communicate with the server for the BI Instance.

Action:
Ensure that the server for the BI Instance is running.

EM-02658
The {1} operation can not be performed on the {0} component.

Category:
Enterprise Manager

Cause:
The specified Oracle Business Intelligence component failed to respond to the operation.

Action:
See the log files for the Oracle Business Intelligence component to determine the cause of the error.

EM-02668
The configuration for BI Instance can not be locked.

Category:
Enterprise Manager

Cause:
The BI Instance was already locked by another user.

Action:
Determine which user has locked the BI Instance and request that it be released.

EM-02669
The changes to the BI Instance can not be committed.

Category:
Enterprise Manager

Cause:
The BI Instance failed to commit all recent changes.

Action:
See the log files for the BI Instance to determine the cause of the error.

EM-02670
The changes to the BI Instance can not be reverted.

Category:
Enterprise Manager

Cause:
The BI Instance failed to revert all recent changes.

Action:
See the log files for the BI Instance to determine the cause of the error.

EM-02672
The BI Instance can not be started.

Category:
Enterprise Manager

Cause:
The BI Instance could not respond correctly to the start command.

Action:
See the log files for the BI Instance to determine the cause of the error.

EM-02673
The BI Instance can not be stopped.

Category:
Enterprise Manager

Cause:
The BI Instance could not respond correctly to the stop command.

Action:
See the log files for the BI Instance to determine the cause of the error.

EM-02674
The BI Instance can not be restarted.

Category:
Enterprise Manager

Cause:
The BI Instance could not respond correctly to the restart command.

Action:
See the log files for the BI Instance to determine the cause of the error.

9
ESS-00001 to ESS-09422

ESS-00001
Internal error. {0}

Category:
Other

Cause:
Internal error occurred.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-00002
Constraint error for property {0} with value {1}.

Category:
Other

Cause:
An attempt was made to create an object that already exists. An attempt was made to change the value of an object thatis read-only.

Action:
Specifiy an identifier for the object that is not currently in use. Retry the operation without changing the value of the object.

ESS-00003
Failed to find resource {0}. {1}

Category:
Other

Cause:
A JNDI lookup of the given resource failed.

Action:
Ensure the resource is deployed properly and is available via jndi lookup.

ESS-00004
Incorrect timestamp format: {0}. {1}

Category:
Programmatic

Cause:
An invalid value was specified for a timestamp.

Action:
Specify a correct value for the parameter.

ESS-00005
SQL bind operation not supported for parameter data type: {0}

Category:
Programmatic

Cause:
A value being used for an SQL bind parameter has a data type that is not suitable for the SQL Statement.

Action:
Specify a parameter value having an appropriate data type.

ESS-00006
Enterprise Scheduler configuration is not initialized.

Category:
Programmatic

Cause:
An operation attempted to access Enterprise Scheduler configuration information before the configuration was initialized.

Action:
Re-try the operation at a later time.

ESS-00007
Operation intended for group, {0}. Configured group is {1}.

Category:
Other

Cause:
An Enterprise Scheduler instance received an event, message, or other data that was intended for an instance of a different group.

Action:
Contact Oracle Support Services.

ESS-00100
Install plan is not present for application {0}.

Category:
Installation

Cause:
The install plan is not present for the application being deployed.

Action:
Contact Oracle Support Services.

ESS-00101
Global data source, {0}, could not be created.

Category:
Installation

Cause:
The global data source could not be created.

Action:
Check the underlying cause for details.

ESS-00102
Dependent component, {0}, has not been deployed.

Category:
Installation

Cause:
A dependent component of this component has not been deployed. An error may have occurred when deploying dependent component.

Action:
Check log for errors in deploying dependent component.

ESS-00103
Error finding application {0}.

Category:
Installation

Cause:
An error occurred while attempting to find the specified application.

Action:
Perform the action specified in the chained exception.

ESS-00104
Cannot find object {0} for archive {1}.

Category:
Other

Cause:
The attempt to access the specified object failed.

Action:
None

ESS-00120
Invalid value for dispatcher poll interval.

Category:
Other

Cause:
Attempted to configure an invalid value for the dispatcher minimum or maximum poll interval.

Action:
Retry the operation with a non-negative numeric value.

ESS-00121
Dispatcher poll interval minimum value cannot exceed maximum value.

Category:
Other

Cause:
Attempted to configure a value for the dispatcher minimum poll interval that is greater than the maximum value. Attempted to configure a value for the dispatcher maximum poll interval that is less than the minimum value.

Action:
Retry the operation with a value that is less than or equal to the maximum value. Retry the operation with a value that is equal to or greater than the minimum value.

ESS-00122
Invalid value for processor threads.

Category:
Other

Cause:
Attempted to configure an invalid value for the processor maximum threads.

Action:
Retry the operation with a non-negative numeric value.

ESS-00123
Invalid value for processor starvation threshold.

Category:
Other

Cause:
Attempted to configure an invalid value for the processor starvation threshold.

Action:
Retry the operation with a non-negative numeric value.

ESS-00124
Unable to validate metadata for work assignment {0}.

Category:
Other

Cause:
Attempted to add or remove bindings for an work assignment.

Action:
Retry the operation with a valid work assignment name.

ESS-00500
Failed to create metadata service handle.

Category:
Other

Cause:
An error occurred while starting a Metadata session.

Action:
See the base exception for details.

ESS-00501
Failed to close metadata service handle.

Category:
Other

Cause:
An error occurred while closing a Metadata session.

Action:
See the base exception for details.

ESS-00502
The metadata object type must be specified

Category:
Other

Cause:
The metadata type was not specified when creating the metadata object

Action:
Specify a valid value for the metadata object type

ESS-00503
MetadataServiceHandle is null.

Category:
Programmatic

Cause:
The ESS metadata service handle is null.

Action:
Specify a valid ESS metadata service handle.

ESS-00800
Error attempting notification for SQL job request {0}.

Category:
Other

Cause:
Failed to create notification that SQL job executable completed.

Action:
Review the log file to determine the nature of the problem.

ESS-01000
Failed to open runtime service. {0}

Category:
Programmatic

Cause:
An error occurred opening the RuntimeService handle

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01001
Failed to close runtime service handle. {0}

Category:
Programmatic

Cause:
An error occurred closing the RuntimeService handle

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01002
Illegal attempt to validate request, {0}, when current state, {1}, is not PENDING_VALIDATION.

Category:
Other

Cause:
A request is in an illegal state for validation.

Action:
None

ESS-01003
Illegal operation for an unvalidated request {0}.

Category:
Programmatic

Cause:
The operation is not supported for an unvalidated request.

Action:
Do not attempt this operation unless the request is validated.

ESS-01004
Illegal attempt to set state of request, {0}, to VALIDATION_FAILED when current state, {1}, is not PENDING_VALIDATION.

Category:
Other

Cause:
An internal error occurred.

Action:
None

ESS-01005
Parameter {0} does not exist for request {1}.

Category:
Programmatic

Cause:
The given parameter name does not exist for this request.

Action:
Specify an existing parameter.

ESS-01006
RuntimeServiceHandle is marked for rollback only.

Category:
Programmatic

Cause:
The ESS runtime service handle has been marked for rollback only.

Action:
Close the ESS runtime service session. Another session may be created for further operations.

ESS-01007
RuntimeServiceHandle is null.

Category:
Programmatic

Cause:
The ESS runtime service handle is null.

Action:
Specify a valid ESS runtime service handle.

ESS-01008
Value for parameter, {0}, has an invalid data type: {1}.

Category:
Programmatic

Cause:
The value for a parameter has an unsupported data type.

Action:
Specify a value which has a supported data type for the parameter.

ESS-01009
Value for parameter, {0}, is not valid.

Category:
Programmatic

Cause:
The value for a parameter is not valid.

Action:
Specify a valid value for the parameter.

ESS-01010
Value for parameter, {0}, must not be null.

Category:
Programmatic

Cause:
The given parameter does not support a null value, or empty string for string parameter.

Action:
Specify a non-null value for the parameter.

ESS-01011
Parameter, {0}, is required but was not specified.

Category:
Programmatic

Cause:
The given parameter is required but was not specified.

Action:
Specify the required parameter.

ESS-01012
Request {0} not found.

Category:
Programmatic

Cause:
A request that was the target of a RuntimeService operation was not found in the runtime store.

Action:
Specify a valid request identifier.

ESS-01013
Failed to lock request {0}. Request not found.

Category:
Programmatic

Cause:
Attemped to lock a request that was not found in the runtime store.

Action:
Specify a valid request identifier.

ESS-01014
Error occurred attempting to lock request {0}.

Category:
Other

Cause:
An error occurred attempting to lock a request in the runtime store.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01015
Failed to generate a request identifier.

Category:
Other

Cause:
An error occurred attempting to generate a new request identifier.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01016
Failed to generate a request handle.

Category:
Other

Cause:
An error occurred attempting to generate a new request handle.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01017
Error attempting to access information for request {0}.

Category:
Other

Cause:
An error occurred attempting to access information for a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01018
Error attempting to update information for request {0}.

Category:
Other

Cause:
An error occurred attempting to update information for a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01019
Request {0} is not in {1} state. Current state is {2}.

Category:
Programmatic

Cause:
An operation was attempted when the request was not in an expected state.

Action:
Retry the operation when the request is the correct state.

ESS-01021
Failed to create DMS context for new request.

Category:
Programmatic

Cause:
Failed to create a DMS context for a new request.

Action:
Review any linked exceptions to identify the root cause of the error.

ESS-01022
Error occurred retrieving summary data. {0}

Category:
Other

Cause:
An error occurred attempting to retrieve request or application summary information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01023
Parameter {0} for request {1} is read-only.

Category:
Programmatic

Cause:
Attempted to modify the value for a request parameter that is read-only.

Action:
None

ESS-01024
This operation is illegal for this request. {0}

Category:
Programmatic

Cause:
The invoked operation is not legal for this request.

Action:
None

ESS-01025
The request does not have a schedule. {0}

Category:
Programmatic

Cause:
This operation can only be applied to a request with a schedule.

Action:
None

ESS-01026
Schedule for request {0} cannot be changed when in state {1}

Category:
Programmatic

Cause:
The schedule for this request cannot be replaced in the current state.

Action:
None

ESS-01027
Failed to convert schedule to string

Category:
Programmatic

Cause:
The schedule cannot be converted to a string.

Action:
None

ESS-01028
Request submission or validation failed. {0}

Category:
Programmatic

Cause:
An error occurred during request submission or validation.

Action:
None

ESS-01029
Failed to create child request for parent request {0}.

Category:
Programmatic

Cause:
An error occurred while attempting to create a child request for a parent that was submitted with a Schedule or Trigger.

Action:
None

ESS-01030
Failed to create JobSet step request for parent request {0}, step {1}.

Category:
Programmatic

Cause:
An error occurred while attempting to create a request for a JobSet step.

Action:
None

ESS-01031
Application {0} was not found.

Category:
Programmatic

Cause:
Attempted to submit a request for an application associated with a logical name but no such application was found.

Action:
Deploy the application

ESS-01032
Application {0} was found in more than one process group.

Category:
Programmatic

Cause:
Attempted to submit a request for an application that is deployed to multiple process groups. Unable to determine correct group to use.

Action:
Application should be deployed to only one group.

ESS-01033
Application {0} was not found for process group {1}.

Category:
Programmatic

Cause:
Attempted to submit a request for an application that is deployed to multiple process groups. Unable to determine correct group to use.

Action:
Application should be deployed to only one group.

ESS-01034
Unable to determine the deployed application name for logical application {0}.

Category:
Programmatic

Cause:
Unable to determine the name of the deployed application for the specified logical name.

Action:
Check for deployment errors.

ESS-01035
Unable to determine a logical application name for new request.

Category:
Programmatic

Cause:
Unable to determine the logical application that should be used for a submitted request.

Action:
Specify a value for the SystemProperty.EFFECTIVE_APPLICATION parameter in the metatadata for the JobDefinition or JobSet.

ESS-01036
Unable to determine a process group for new request.

Category:
Programmatic

Cause:
Unable to determine the process group that should be used for a submitted request.

Action:
None

ESS-01037
Job definition is required for a non-Adhoc request submission.

Category:
Programmatic

Cause:
A submit operation was attempted for a non-adhoc job but no metadata id for a JobDefinition or JobSet was given.

Action:
Retry the submit operation and specify a job defintion.

ESS-01038
Read-Only violation for request parameter {0}.

Category:
Programmatic

Cause:
The given parameter is marked as read-only and was specified as a request parameter.

Action:
Retry the operation without the parameter.

ESS-01039
Parameter, {0}, is not allowed in request submission parameters.

Category:
Programmatic

Cause:
The given parameter is not allowed to be included as a request parameter for a submit operation. Usually such paramters can be set only via a metadata parameter.

Action:
Retry the operation without the given parameter.

ESS-01040
Invalid parameter {0}. Scoped parameters are only supported for JobSet.

Category:
Programmatic

Cause:
A scoped parameter was included in the request parameters specified for the request submisssion of a JobDefinition. Scoped parameters are supported only for a JobSet.

Action:
Retry the submit operation without the scoped parameter.

ESS-01041
Parameter, {0}, is not allowed as a scoped request parameter for JobSet step {1}.

Category:
Programmatic

Cause:
The request parameters for a JobSet submission include a scoped parameter that is not allowed to be specified as a scoped parameter for a JobSet step.

Action:
Retry the submit operation without the scoped parameter.

ESS-01042
Metadata type, {0}, is not supported for a sub-request.Only JobDefinition is supported.

Category:
Programmatic

Cause:
Attempted to submit a sub-request for an unsupported definition type. Subrequest supported only for a JobDefinition.

Action:
Retry the operation using a valid defintion type.

ESS-01043
Failed to get XML for an adhoc Schedule.

Category:
Programmatic

Cause:
Error occurred creating XML representation of an adhoc Schedule.

Action:
Fix the adhoc Schedule and retry the operation.

ESS-01046
Start time must be before the end time.

Category:
Programmatic

Cause:
Attempted to submit a request where the start time is after the end time.

Action:
Retry the operation with valid start and end times.

ESS-01047
End time must be after the current time.

Category:
Programmatic

Cause:
Attempted to submit a request where the end time is before the current time.

Action:
Retry the operation with value end time.

ESS-01048
Schedule has expired and no executions are possible.

Category:
Programmatic

Cause:
Attempted to submit a request with a Schedule that has expired.

Action:
Retry the operation with a different Schedule.

ESS-01049
No executions are possible before the given end date.

Category:
Programmatic

Cause:
Attempted to submit a request with a Schedule for which there no executions prior to the end date.

Action:
Retry the operation with a different Schedule.

ESS-01050
One or more requests are currently pending for definition: {0}

Category:
Programmatic

Cause:
The SystemProperty.ALLOW_MULT_PENDING property is disabled for the request being submitted. Execution is already pending for one or more requests with the same job definition.

Action:
None

ESS-01051
Incompatible with parent request {0} due to Incompatibility definition: {1}

Category:
Programmatic

Cause:
Attempted to submit a sub-request that is incompatible with its parent request due to an Incompatibility definition

Action:
None

ESS-01052
Request handle is not valid for the current execution context of parent request {0}.

Category:
Programmatic

Cause:
The SystemProperty.ALLOW_MULT_PENDING property is disabled for the request being submitted. Execution is already pending for one or more requests with the same job definition.

Action:
None

ESS-01053
Cannot cancel request {0}. Current state is {1}.

Category:
Programmatic

Cause:
Attempted to cancel a request whose current state does not allow the operation to be performed.

Action:
None

ESS-01054
Cannot hold request {0}. Current state is {1}.

Category:
Programmatic

Cause:
Attempted to hold a request whose current state does not allow the operation to be performed.

Action:
None

ESS-01055
Cannot release request {0}. Current state is {1}.

Category:
Programmatic

Cause:
Attempted to release a request whose current state does not allow the operation to be performed.

Action:
None

ESS-01056
Cannot delete request {0}. Current state is {1}, process phase is {2}.

Category:
Programmatic

Cause:
Attempted to delete a request whose current state or process phase does not allow the operation to be performed.

Action:
Retry the operation at a later time.

ESS-01057
Cannot purge request {0}. Current state is {1}, process phase is {2}.

Category:
Programmatic

Cause:
Attempted to purge a request whose current state or process phase does not allow the operation to be performed.

Action:
Retry the operation at a later time.

ESS-01058
Cannot change priority for request {0}. Current state is {1}.

Category:
Programmatic

Cause:
Attempted to change the priority for a request whose current state does not allow the operation to be performed.

Action:
None

ESS-01059
Delete failed for request {0}. This operation is not supported for a sub-request or JobSet step.

Category:
Programmatic

Cause:
Attempted to perform a delete operation on a child request. Only an absolute parent or instance parent can be the target of a delete operation.

Action:
None

ESS-01060
Purge failed for request {0}. This operation not supported for a sub-request or JobSet step.

Category:
Programmatic

Cause:
Attempted to perform a purge operation on a child request. Only an absolute parent or instance parent can be the target of a purge operation.

Action:
None

ESS-01061
Failed to purge request {0}.

Category:
Programmatic

Cause:
An error occurred attempting to purge a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01062
Invalid priority value. Valid range is {0} to {1}.

Category:
Programmatic

Cause:
An invalid value for request priority is specified.

Action:
Specify a value in the indicated range.

ESS-01063
Failed to retrieve Schedule for request {0}.

Category:
Programmatic

Cause:
Failed to retrieve the Schedule associated with the given request.

Action:
None

ESS-01065
Cannot recover request {0} with incomplete child requests.

Category:
Programmatic

Cause:
An attempt was made to manually recover a request with at least one child not in ProcessPhase.Complete.

Action:
Wait for the incomplete child to complete or recover.

ESS-01066
Request state {0} not allowed for manual recovery. State should be canceling or terminal. {1}

Category:
Programmatic

Cause:
An attempt was made to manually recover a request that was in an illegal state.

Action:
Cancel the request.

ESS-01067
Error occurred mapping Filter to CompositeData.

Category:
Programmatic

Cause:
Error occurred mapping Filter to CompositeData.

Action:
Correct the invalid CompositeData instance.

ESS-01068
Unexpected type, {0}, for Filter value {1}.

Category:
Programmatic

Cause:
Unexpected Filter type for Filter value.

Action:
Correct the invalid Filter type.

ESS-01069
Invalid Null input for a Filter {0}.

Category:
Programmatic

Cause:
Unexpected null input for a filter.

Action:
Provider a non null value.

ESS-01070
Cannot change start time or end time for request of type {0}

Category:
Programmatic

Cause:
The start and end times cannot be updated for a request this type.

Action:
None

ESS-01071
Schedule for request {0} cannot be for a retry attempt

Category:
Programmatic

Cause:
The schedule for this request cannot be replaced during a retry.

Action:
None

ESS-01072
Metadata schedule and adhoc schedule were specified. Only one schedule can be used.

Category:
Programmatic

Cause:
A metadata schedule and an adhoc schedule were specified for an operation. Only one schedule should be specified.

Action:
Retry the operation with only one schedule

ESS-01073
Failed to open runtime service: {0}. {1}

Category:
Programmatic

Cause:
An error occurred opening the RuntimeService handle

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01074
Failed to open runtime service due to resource error. {0}

Category:
Programmatic

Cause:
A resource error occurred opening the RuntimeService handle.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01075
Cannot delete execution group, {0}, because active instances exist.

Category:
Programmatic

Cause:
A execution group must not be deleted when active instances exist in its cluster.

Action:
Use only when the cluster associated with the execution group no longer exists.

ESS-01076
Execution group {0} is already being deleted.

Category:
Programmatic

Cause:
The execution group is already being deleted.

Action:
Wait for first deletion to complete.

ESS-01077
Failed to get async request information for message {0}.

Category:
Other

Cause:
Failed to retrieve information for web service asynchronous callback.

Action:
Check the logs.

ESS-01078
Request {0} is required to be asynchronous for this operation.

Category:
Other

Cause:
This operation cannot be executed on a synchronous request.

Action:
Do not invoke the operation on this request.

ESS-01079
Error attempting to access request information.

Category:
Other

Cause:
An error occurred attempting to access request information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01080
Failed to persist request information.

Category:
Other

Cause:
An error occurred attempting to persist request information to the runtime store.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01081
Failed to persist request parameter {0}, scope {1}.

Category:
Other

Cause:
An error occurred attempting to store a request parameter.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01082
Failed to persist read-only constraint for parameter {0}.

Category:
Other

Cause:
An error occurred attempting to store parameter read-only constraint.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01083
Error attempting to retrieve parameters for request {0}.

Category:
Other

Cause:
An error occurred attempting to retrieve request parameters.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01084
Error attempting to update parameter, {0}, for request {1}.

Category:
Other

Cause:
An error occurred attempting to update a request parameter.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01085
Failed to add parameter {0}, scope {1}, for request {2}.

Category:
Other

Cause:
An error occurred attempting to add a request parameter.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01086
Operation not supported for scoped parameter, {0}.

Category:
Programmatic

Cause:
A scoped parameter was specified for an operation that is not supported for scoped parameter.

Action:
None

ESS-01087
Failed to convert Document to byte sequence.

Category:
Other

Cause:
An error occurred converting a Document to byte sequence.

Action:
None

ESS-01088
Failed to convert byte sequence to Document.

Category:
Other

Cause:
An error occurred converting a byte sequence to a Document.

Action:
None

ESS-01089
Failed to get storable value for parameter, {0}.

Category:
Other

Cause:
An error occurred converting a parameter value to its stored representation.

Action:
None

ESS-01090
Failed to get typed value for parameter, {0}, data type, {1}.

Category:
Other

Cause:
An error occurred converting a parameter value from its stored representation to a typed value.

Action:
None

ESS-01091
Unable to obtain incompatibility value for property, {0}.

Category:
Programmatic

Cause:
Unable to materialize an incompatibility value for the specified property.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01092
Incompatibility conflict detected between request {0} and parent request {1} for incompatibility {2}.

Category:
Other

Cause:
Incompatibility conflict detected between a JobSet step request and a JobSet request of its parent chain. An incompatibility lock for that incompatibility will not be acquired for the step request.

Action:
None

ESS-01093
Number of acquired request incompatibilities ({0}) does not match number of incompatibility locks ({1}) for request {2}.

Category:
Other

Cause:
Runtime service system failure.

Action:
Review the log file for underlying causes.

ESS-01094
Error attempting to process getCompletionStatus call since another getCompletionStatus call with message id {0} is pending for reply.

Category:
Other

Cause:
An error occured attempting to process getCompletionStatus call since another getCompletionStatus call with messageid {0} is pending for reply.

Action:
Attach different ws message id or wait for the previous call finished before submit getCompletionStatus call.

ESS-01095
Unable to find ess hosting app with logical application name {0}.

Category:
Programmatic

Cause:
Unable to find ess hosting app with logical application name {0}.

Action:
Specify a correct parameter of application or deploy the ess hosting app with expected logical application name.

ESS-01096
Query result handle is null.

Category:
Programmatic

Cause:
The value of the query result handle argument is null.

Action:
Specify an argument value that is not null.

ESS-01097
Request, {0}, is not of expected type, {1}.

Category:
Programmatic

Cause:
The request was found in ESS runtime storage but was not of the expected execution type.

Action:
Specify a request identifier for a request of the correct execution type.

ESS-01098
No request is found for id {0} {1}

Category:
Programmatic

Cause:
A request was not found in ESS runtime storage corresponding to the indicated request identifier.

Action:
Specify a request identifier for an existing request.

ESS-01099
An error occurred invoking the RuntimeService MBean. {0}

Category:
Programmatic

Cause:
An error occurred invoking the RuntimeService MBean.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01100
Error retrieving details about Oracle Scheduler job {0} for request {1}.

Category:
Programmatic

Cause:
An error occurred while trying to retrieve details about the Oracle Scheduler job associated with an ESS request identifier.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01101
Error retrieving the OUTPUT_LIST for parallel children of request {0}.

Category:
Programmatic

Cause:
An error occurred while trying to retrieve the OUTPUT_LIST for parallel child requests for an ESS request identifier.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01102
Failed to register application, {0}, with instance {1}. {2}

Category:
Other

Cause:
Application registration failed with ESS.

Action:
Contact Oracle Support Services.

ESS-01103
Failed to unregister all applications for instance {0}. {1}

Category:
Other

Cause:
Application deregistration failed with ESS.

Action:
Contact Oracle Support Services.

ESS-01104
Failed to unregister application, {0}, for instance {1}. {2}

Category:
Other

Cause:
Application deregistration failed with ESS.

Action:
Contact Oracle Support Services.

ESS-01105
Failed to check in instance {0}. {1}

Category:
Other

Cause:
Registration update of ESS instance failed.

Action:
Check that database is running and data source is correct.

ESS-01106
Failed to clear checkin entry for instance {0}. {1}

Category:
Other

Cause:
Unregistration of ESS instance failed.

Action:
Check that database is running and data source is correct.

ESS-01107
Failed to remove timed out instance registrations. {0}

Category:
Other

Cause:
Unregistration of ESS timed-out instances failed.

Action:
Check that database is running and data source is correct.

ESS-01108
Failed to fetch elements from wait queue. {0}.

Category:
Other

Cause:
An error occurred attempting to fetch elements from the wait queue.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01109
Failed to access wait queue element for request {0}. {1}

Category:
Other

Cause:
An error occurred attempting to access a wait queue element.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01110
Failed to lock wait queue element for request {0}. {1}

Category:
Other

Cause:
Failed to obtain a lock on the wait queue element for a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01111
Failed to insert wait queue element for request {0}. {1}

Category:
Other

Cause:
An error occurred while attempting to add an element to the wait queue.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01112
Failed to delete wait queue element for request {0}. {1}

Category:
Other

Cause:
An error occurred while attempting to remove an element from the wait queue.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01113
Failed to hold wait queue element for request {0}. {1}

Category:
Other

Cause:
An error occurred attempting to hold the wait queue element for a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01114
Failed to release wait queue element for request {0}. {1}

Category:
Other

Cause:
An error occurred attempting to release the wait queue element for a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01115
Failed to undefer wait queue element for request {0}. {1}

Category:
Other

Cause:
An error occurred attempting to undefer the wait queue element for a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01116
Query field name, {0}, is not a valid name.

Category:
Programmatic

Cause:
A query filter was specified with an unknown query field.

Action:
Remove that query field from the filter, or specify a known name for the query field.

ESS-01117
Value for query field, {0}, has an unsupported data type: {1}

Category:
Programmatic

Cause:
A query filter was specified in which the value for a query field has an unsupported data type.

Action:
Specify a query value whose data type is a supported type.

ESS-01118
Query field, {0}, has a null value which is not supported for the {1} operator.

Category:
Programmatic

Cause:
A query filter was specified with a field that has a null value and a comparator that does not support a null value. A null query value requires an EQUALS or NOT_EQUALS comparator.

Action:
Specify a non-null value for that query field, or specify an EQUALS or NOT_EQUALS comparator.

ESS-01119
Query field, {0}, has a value with a data type, {1}, that is not supported for the {2} comparator.

Category:
Programmatic

Cause:
A query filter was specified with a field that has a value whose data type is not supported for the specified comparator.

Action:
Specify a query value whose data type is supported by the comparator being used.

ESS-01120
Query field, {0}, does not support the {1} comparator.

Category:
Programmatic

Cause:
A query filter was specified with a field that does not support the specified comparator.

Action:
Specify a comparator that is supported by that query field.

ESS-01121
Failed to retrieve field {0}.

Category:
Programmatic

Cause:
A failure occurred while retrieving the specified field.

Action:
Check that database is running and data source is correct.

ESS-01122
Error attempting to access information for incompatibility {0} for request {1}.

Category:
Programmatic

Cause:
An error occurred attempting to access request incompatibility information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01123
Error attempting to update information for incompatibility {0} for request {1}.

Category:
Programmatic

Cause:
An error occurred attempting to update request incompatibility information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01124
Error attempting to add information for incompatibility {0} for request {1}.

Category:
Programmatic

Cause:
An error occurred attempting to add request incompatibility information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01125
Size of request parameter {0} used for incompatibility {1} is too large.

Category:
Programmatic

Cause:
The value for a request parameter that would be used for an Incompatibility is too large.

Action:
Use a smaller value for the parameter value.

ESS-01126
Application {0} is active in more than one group.

Category:
Programmatic

Cause:
An application with the same name is already a member of another ESS group.

Action:
Redeploy the current application with a unique deployment name.

ESS-01127
Application {0} is not active in any ESS instance.

Category:
Programmatic

Cause:
The application could not be found in the current ESS group.

Action:
Ensure the application is deployed and running in the correct ESS group.

ESS-01128
Application with deployed name {0} exists with multiple logical names.

Category:
Programmatic

Cause:
An application with the same deployment name but different logical name is already a member of this ESS group.

Action:
Redploy this application with a unique deployment name. If this application is the same application as the conflicting app, then change the logical name to match.

ESS-01129
Application with logical name {0} was not found.

Category:
Programmatic

Cause:
The application is not a member of this ESS group.

Action:
Ensure the application is deployed and running in the correct ESS group.

ESS-01130
Application with logical name {0} exists with multiple deployed names.

Category:
Programmatic

Cause:
An application with the same logical name but different deployment name is already a member of this ESS group.

Action:
Redploy this application with a unique logical application name. If this application is the same application as the conflicting app, then change the deployment name to match.

ESS-01131
Application with deployed name {0} was not found.

Category:
Programmatic

Cause:
The application is not a member of this ESS group.

Action:
Ensure the application is deployed and running in the correct ESS group.

ESS-01132
Unable to access processor bindings. {0}

Category:
Other

Cause:
Processor bindings in the runtime store could not be accessed.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01133
Processor binding {0} could not be found.

Category:
Other

Cause:
Processor binding could not be found.

Action:
Check that you specified the correct binding name.

ESS-01134
Processor binding {0} already exists.

Category:
Other

Cause:
Processor binding already exists.

Action:
Change the name of the binding.

ESS-01135
Unable to notify server of processor bindings change. {0}

Category:
Other

Cause:
Unable to notify server of bindings change.

Action:
Check that database is running and data source is correct.

ESS-01136
Unable to access processor bindings change notification. {0}

Category:
Other

Cause:
Unable to access bindings change notification.

Action:
Check that database is running and data source is correct.

ESS-01137
Unable to notify server to refresh selector. {0}

Category:
Other

Cause:
Unable to notify server to refresh selector.

Action:
Check that database is running and data source is correct.

ESS-01138
Unable to access refresh selector notification. {0}

Category:
Other

Cause:
Unable to access refresh selector notification.

Action:
Check that database is running and data source is correct.

ESS-01139
Value, {1}, for query field, {0}, is invalid.

Category:
Programmatic

Cause:
A query filter was specified in which the value for a query field was invalid.

Action:
Specify a valid query value.

ESS-01140
Error accessing async throttle information for ({0}, {1}). {2}

Category:
Other

Cause:
An error occurred while accessing runtime async throttle information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01141
Async throttle already exists for Workshift = {0}. {1}

Category:
Other

Cause:
The throttle is already configured for the Workshift.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01142
Async throttle not found for Workshift = {0}.

Category:
Other

Cause:
The throttle was not found for the Workshift.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01143
Failed to process filter {0}.

Category:
Programmatic

Cause:
Filter evaluation failed.

Action:
Correct the invalid Filter.

ESS-01144
Failed to retrieve timed out instance registrations. {0}

Category:
Other

Cause:
Query of ESS timed out registrationsinstance failed.

Action:
Check that database is running and data source is correct.

ESS-01145
Failed to lock instance {0}. {1}

Category:
Other

Cause:
Locking the ESS instance registration failed.

Action:
Check that database is running and data source is correct.

ESS-01146
Error accessing runtime async throttle information. {0}

Category:
Other

Cause:
An error occurred while accessing the throttle configuration.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01147
Failed to get DiagnosticState for instance {0}. {1}

Category:
Other

Cause:
Failed to get DiagnosticState for the instance.

Action:
None

ESS-01148
Failed to clear registrations for execution group {0}, isolation group {1}. {2}

Category:
Other

Cause:
Failed to clear registrations for execution group.

Action:
None. Registrations will be automatically retried

ESS-01149
Error accessing unthrottled work assignments ({0}). {1}

Category:
Other

Cause:
An error occurred while accessing the unthrottled work assignments.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01150
Unable to delete workshift with outstanding async workers: {0}

Category:
Other

Cause:
A workshift that has outstanding async workers not be deleted.

Action:
Wait until all async workers have completed and then delete the workshift.

ESS-01151
Error accessing async limit information for workshift = {0}. {1}

Category:
Other

Cause:
An error occurred while accessing runtime async limit information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01152
Error accessing async allocation information for work assignment = {0}. {2}

Category:
Other

Cause:
An error occurred accessing runtime async allocation information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01153
Failed to add incompatibility lock {0}.

Category:
Programmatic

Cause:
An error occurred attempting to add incompatibility lock information.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01154
Failed to delete incompatibility lock {0}.

Category:
Programmatic

Cause:
An error occurred attempting to delete incompatibility lock information.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01155
Failed to lock incompatibility lock {0}.

Category:
Programmatic

Cause:
An error occurred attempting to delete incompatibility lock information.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01156
Failed to update reference count for incompatibility lock {0}.

Category:
Programmatic

Cause:
An error occurred attempting to delete incompatibility lock information.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01157
Failed to retrieve incompatibility locks for request {0}.

Category:
Programmatic

Cause:
An error occurred attempting to retrieve incompatibility locks held by a request.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01158
Failed to lock incompatibility locks for request {0}.

Category:
Programmatic

Cause:
An error occurred attempting to lock any incompatibility locks held by a request.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01159
Failed to retrieve request incompatibility for request {0}.

Category:
Programmatic

Cause:
An error occurred attempting to retrieve request incompatibility information.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01160
Failed to lock request incompatibility for request {0}.

Category:
Programmatic

Cause:
An error occurred attempting to lock request incompatibility information.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01161
Failed to retrieve request incompatibility.

Category:
Programmatic

Cause:
An error occurred attempting to retrieve request incompatibility information.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01162
Failed to lock request incompatibility.

Category:
Programmatic

Cause:
An error occurred attempting to lock request incompatibility information.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01163
Failed to add reference for incompatibility {0}, job definition {1}, request {2}.

Category:
Programmatic

Cause:
An error occurred attempting to add job incompatibility reference.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01164
Reference already exists for incompatibility {0}, job definition {1}, request {2}.

Category:
Programmatic

Cause:
Job incompatibility reference already exists.

Action:
None

ESS-01165
Failed to retrieve incompatibility metadata from runtime store for job definition {0}, request {1}.

Category:
Programmatic

Cause:
An error occurred attempting to retrieve incompatibility metadata from runtime store for a job definition.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01166
Query for application registration information failed.

Category:
Other

Cause:
An error occurred while querying the application registration table.

Action:
Contact Oracle Support Services

ESS-01167
Failed to cache metadata in runtime store for request {0}, metadata {1}.

Category:
Other

Cause:
An error occurred while saving metadata in the ESS runtime store.

Action:
Review the log file to determine the nature of the problem.

ESS-01168
Binding mode conflict for {0}

Category:
Other

Cause:
Binding mode conflict. Work assignment may be bound in either standard or exclusive mode, but not in both modes on two different servers in the same processing group.

Action:
Use the correct binding mode.

ESS-01169
Workshift does not exist {0}

Category:
Other

Cause:
The workshift does not exist.

Action:
Ensure you are using the correct workshift name, and that the workshift exists.

ESS-01170
Failed to retrieve runtime store information.

Category:
Other

Cause:
An error occurred attempting to retrieve runtime store information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01171
Runtime store compatibility information is not available.

Category:
Other

Cause:
Unable to retrieve Enterprise Scheduler Service runtime store compatibility information.

Action:
Contact Oracle Support Services.

ESS-01172
Runtime store compatibility check failed; mid-tier check version: {0}, runtime store version: {1}, schema name: {2}

Category:
Other

Cause:
The Enterprise Scheduler Service mid-tier is not compatible with the database runtime store.

Action:
Upgrade database schema or mid-tier to be compatible

ESS-01173
Runtime store status check failed; runtime store status: {0}, schema name: {1}

Category:
Other

Cause:
The Enterprise Scheduler Service runtime store is not valid.

Action:
Contact Oracle Support Services.

ESS-01174
Runtime store compatibility check failed; mid-tier check version: {0}, runtime store version: {1}, schema name: {2}. Check disabled, allowing operation to continue.

Category:
Other

Cause:
The Enterprise Scheduler Service mid-tier is not compatible with the database runtime store.

Action:
Upgrade database schema or mid-tier to be compatible.

ESS-01175
Runtime store status check failed; runtime store status: {0}, schema name: {1}. Check disabled, allowing operation to continue.

Category:
Other

Cause:
The Enterprise Scheduler Service runtime store is not valid.

Action:
Contact Oracle Support Services.

ESS-01176
Triggers are not supported.

Category:
Programmatic

Cause:
A trigger was specified to the metadata service or when submitting a request.

Action:
Do not create triggers and specify a null value for any trigger parameter.

ESS-01177
Failed to delete job incompatibility references for request {0} from runtime store.

Category:
Programmatic

Cause:
An error occurred attempting to remove job incompatibility references.

Action:
Review the causeBy exception chain to determine the specific failure.

ESS-01178
Query for server coordination information failed.

Category:
Other

Cause:
An error occurred while querying the server coordination table.

Action:
Check that database is running and data source is correct.

ESS-01179
Schedule includes explicit times that are before the start time.

Category:
Programmatic

Cause:
Attempted to submit a reuqest with Adhoc schedule that contains time that are before the current time.

Action:
Retry the operation after modifying the times in Adhoc Schedule.

ESS-01180
Unable to determine database type.

Category:
Other

Cause:
Unable to determine the database type being used for the runtime store.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01181
Failed to delete information for request {0}.

Category:
Other

Cause:
An error occurred attempting to remove request information from the runtime store.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01182
Failed to update wait queue element for request {0}.

Category:
Other

Cause:
An error occurred attempting to update the wait queue element for a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01183
Wait queue operation failed.

Category:
Other

Cause:
An error occurred attempting a wait queue operation.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01184
Update of server coordination information failed.

Category:
Other

Cause:
An error occurred attempting to update the server coordination table.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01185
Failed to get async request information for request {0}.

Category:
Other

Cause:
Failed to retrieve information for web service asynchronous callback.

Action:
Check the logs.

ESS-01186
Failed to update async request information for message {0}.

Category:
Other

Cause:
Failed to update information for web service asynchronous callback.

Action:
Check the logs.

ESS-01187
Failed to add or modify attribute {0} of namespace {1} for request {2}.

Category:
Other

Cause:
An error occurred attempting to modify request attribute information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01188
Failed to access attribute {0} of namespace {1} for request {2}.

Category:
Other

Cause:
An error occurred attempting to access request attribute information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01189
Failed to delete attribute {0} of namespace {1} for request {2}.

Category:
Other

Cause:
An error occurred attempting to remove request attribute information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01190
Value for attribute {0} of namespace {1} has an invalid data type: {2}.

Category:
Other

Cause:
The value for a request attribute has an unsupported data type.

Action:
Specify a value which has a supported data type for the attribute.

ESS-01191
Failed to get storable value for attribute {0} of namespace {1}.

Category:
Other

Cause:
An error occurred converting a request attribute value to its stored representation.

Action:
None

ESS-01192
Failed to get typed value for attribute {0} of namespace {1} for data type {2}.

Category:
Other

Cause:
An error occurred converting a request attribute value from its stored representation to a typed value.

Action:
None

ESS-01193
Value for attribute {0} of namespace {1} has data type {2} instead of the expected data type {3}

Category:
Other

Cause:
Data type for request attribute value does not match the type already estabished for that attribute.

Action:
None

ESS-01194
An unknown or unsupported request detail type was specified: {0}.

Category:
Other

Cause:
An unknown or unsupported request detail type was specified.

Action:
Provide a valid request detail type.

ESS-01195
Error attempting to access parameter, {0}, for request {1}.

Category:
Other

Cause:
An error occurred attempting to access request parameter information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01196
Unable to get the current time from the database.

Category:
Programmatic

Cause:
Unable to get the current time from the database.

Action:
Review the log file for possible underlying causes.

ESS-01197
Unable to release incompatibility locks for request {0}.

Category:
Programmatic

Cause:
Unable to release one or more incompatibility locks for the request at this time.

Action:
Review the log file for possible underlying causes.

ESS-01198
Unable to obtain configuration information for application {0}.

Category:
Programmatic

Cause:
Unable to retrieve configuration information for application.

Action:
None

ESS-01199
JobSet steps would have mixed request modes: {0}

Category:
Programmatic

Cause:
The steps for a JobSet are not homogeneous in regard to the resolved request mode.

Action:
None

ESS-01200
Error attempting to insert {0} work unit for request {1}.

Category:
Other

Cause:
An error occurred inserting a work unit into the persistent store.

Action:
Review the log file to determine the nature of the problem.

ESS-01201
Error attempting to insert {0} work unit.

Category:
Other

Cause:
An error occurred inserting a work unit into the persistent store.

Action:
Review the log file to determine the nature of the problem.

ESS-01202
Failed to update work stage for work {0}.

Category:
Other

Cause:
An error occurred updating the work stage of a work unit.

Action:
Review the log file to determine the nature of the problem.

ESS-01203
Failed to delete work for request {0}.

Category:
Other

Cause:
An error occurred deleting work units.

Action:
Review the log file to determine the nature of the problem.

ESS-01204
Failed to delete work {0} for request {1}.

Category:
Other

Cause:
An error occurred deleting work units.

Action:
Review the log file to determine the nature of the problem.

ESS-01205
Failed to delete work unit {0}.

Category:
Other

Cause:
An error occurred deleting work units.

Action:
Review the log file to determine the nature of the problem.

ESS-01206
Failed to check in work unit {0} for request {1}.

Category:
Other

Cause:
An error occurred checking in work units.

Action:
Review the log file to determine the nature of the problem.

ESS-01207
Failed to check in work unit {0}.

Category:
Other

Cause:
An error occurred checking in work units.

Action:
Review the log file to determine the nature of the problem.

ESS-01208
Failed to undefer DeleteProcessGroup work for execution group {0}.

Category:
Other

Cause:
An error occurred undeferring a DeleteProcessGroupEvent.

Action:
Review the log file to determine the nature of the problem.

ESS-01209
Failed to update information for work {0} for request {1}.

Category:
Other

Cause:
An error occurred updating a work unit.

Action:
Review the log file to determine the nature of the problem.

ESS-01210
Failed to undefer work for request {0}.

Category:
Other

Cause:
An error occurred undeferring a work unit.

Action:
Review the log file to determine the nature of the problem.

ESS-01211
Failed to check in work for instance {0}.

Category:
Other

Cause:
An error occurred checking in all the work units for an ESS instance.

Action:
Review the log file to determine the nature of the problem.

ESS-01212
Error retrieving available work units.

Category:
Other

Cause:
Error occurred while retrieving work units to process.

Action:
Review the log file for runtime cause.

ESS-01213
Failed to retrieve work unit {0}.

Category:
Other

Cause:
Error occurred while retrieving a work unit to process.

Action:
Review the log file for runtime cause.

ESS-01214
Failed to determine if work {0} is checked out to instance {1}.

Category:
Other

Cause:
Failed to determine if the work is checked out to this instance.

Action:
Review the log file for runtime cause.

ESS-01215
Error occurred querying check out work units for instance {0}.

Category:
Other

Cause:
Failed to determine the work units checked out to the instance.

Action:
Review the log file for runtime cause.

ESS-01216
Failed to access work unit {0}.

Category:
Other

Cause:
Error occurred attempting to access work unit.

Action:
Review the log file for runtime cause.

ESS-01217
Error waiting for work.

Category:
Other

Cause:
Error occurred while waiting for new work.

Action:
Review the log file for runtime cause.

ESS-01218
Error waiting for work. Operation returned: {0}.

Category:
Other

Cause:
Operation used to work for new work returned the specified result.

Action:
Review the log file for runtime cause.

ESS-01219
Work unit {0} is not checked out to instance {1}.

Category:
Other

Cause:
The work unit is not checked out to the specified instance.

Action:
None

ESS-01220
Failed to lock work unit {0} by instance {1}.

Category:
Other

Cause:
Failed to lock the work unit by the specified instance.

Action:
None

ESS-01221
Requests {0} can not be cancelled. Please check server logs for more details.

Category:
Programmatic

Cause:
Requests can not be cancelled as there may be errors in cancelling the requests.

Action:
Please check server logs for more details

ESS-01222
Number of requests that needs to be cancelled in one go, should not exceed max limit of 100 records.

Category:
Programmatic

Cause:
Number of requests that needs to be cancelled in one go, should not exceed max limit of 100 records

Action:
Please provide requests less than 100 records.

ESS-01223
Filter with null value is not supported.Please provide valid filter which includes requests with non-terminal states.

Category:
Programmatic

Cause:
Filter with null value is not supported.

Action:
Please provide valid filters which includes requests with non-terminal states.

ESS-01250
Error retrieving available event work.

Category:
Other

Cause:
Error occurred while retrieving event work to process.

Action:
Review the log file for runtime cause.

ESS-01251
Failed to access event work {0}.

Category:
Other

Cause:
Error occurred attempting to access event work.

Action:
Review the log file for runtime cause.

ESS-01252
Failed to update event work {0}.

Category:
Other

Cause:
Error occurred attempting to update event work.

Action:
Review the log file for runtime cause.

ESS-01253
Failed to delete event work {0}.

Category:
Other

Cause:
Error occurred attempting to delete event work.

Action:
Review the log file for runtime cause.

ESS-01254
Failed to delete event work for request {0}.

Category:
Other

Cause:
Error occurred attempting to delete event work for a request.

Action:
Review the log file for runtime cause.

ESS-01255
Failed to check in event work {0}.

Category:
Other

Cause:
Error occurred attempting to check in event work.

Action:
Review the log file for runtime cause.

ESS-01256
Failed to check in event work for instance {0}.

Category:
Other

Cause:
Error occurred attempting to check in event work for an instance.

Action:
Review the log file for runtime cause.

ESS-01257
Failed to add event. Event name: {0}, request: {1}.

Category:
Other

Cause:
Error occurred attempting to insert event work.

Action:
Review the log file for runtime cause.

ESS-01258
Event work not found: {0}.

Category:
Other

Cause:
The specified event work was not found.

Action:
None

ESS-01259
Error waiting for event work.

Category:
Other

Cause:
Error occurred while waiting for new event work.

Action:
Review the log file for runtime cause.

ESS-01260
Error waiting for event work. Operation returned: {0}.

Category:
Other

Cause:
Operation used to work for new event work returned the specified result.

Action:
Review the log file for runtime cause.

ESS-01262
Event work {0} is not checked out to instance {1}.

Category:
Other

Cause:
The event work is not checked out to a specific instance.

Action:
None

ESS-01263
Invalid event listener class, {0}.

Category:
Other

Cause:
The class name configured for the request listener is not a valid event listener class.

Action:
None

ESS-01264
Unable to instantiate event listener for class, {0}.

Category:
Other

Cause:
Unable to instantiate an instance of an event listener class name.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01265
Unable to retrieve information needed to dispatch an event for request {0}.

Category:
Other

Cause:
Failed to retrieve information needed to dispatch an event.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01266
Failed to lock event work {0} by instance {1}.

Category:
Other

Cause:
Failed to lock the event work by the specified instance.

Action:
None

ESS-01290
Invalid logical cluster name value {0}.

Category:
Other

Cause:
An invalid logical cluster name was specified.

Action:
Specify a valid logical cluster name.

ESS-01291
A logical cluster name is not allowed to contain the character '.'.

Category:
Other

Cause:
An invalid logical cluster name was specified.

Action:
Specify a valid logical cluster name.

ESS-01300
Unable to access content store for request {0}, file {1}. {2}.

Category:
Other

Cause:
Failed to access the content store.

Action:
Review the log file for runtime cause.

ESS-01301
Failed to create content for request {0}, content name {1}. {2}.

Category:
Other

Cause:
Failed to create content for the request.

Action:
Review the log file for runtime cause.

ESS-01302
Failed to update content for request {0}, content name {1}. {2}.

Category:
Other

Cause:
Failed to update content for the request.

Action:
Review the log file for runtime cause.

ESS-01303
Failed to import file to content store for request {0}, file {1}. {2}.

Category:
Other

Cause:
Failed to import file to the content store for the request.

Action:
Review the log file for runtime cause.

ESS-01304
Failed to export content for request {0}, content name {1}. {2}.

Category:
Other

Cause:
Failed to export content for the request.

Action:
Review the log file for runtime cause.

ESS-01305
Failed to delete content for request {0}, content name {1}. {2}.

Category:
Other

Cause:
Failed to delete content for the request.

Action:
Review the log file for runtime cause.

ESS-01306
Failed to delete all content for request {0}. {1}.

Category:
Other

Cause:
Failed to delete all content for the request.

Action:
Review the log file for runtime cause.

ESS-01307
Invalid write to output content for request {0}, content name {1}.

Category:
Other

Cause:
Invalid write to content due to incorrect content type.

Action:
Ensure the type of data you are writing is compatible with the content type.

ESS-01308
The content does not exist for request {0}, content name {1}.

Category:
Other

Cause:
The content does not exist for the request.

Action:
Ensure you are using the correct content name.

ESS-01309
Invalid content handle.

Category:
Other

Cause:
The content handle is invalid.

Action:
Re-open the content and use the valid handle.

ESS-01310
The file does not exist for request {0}, file name {1}.

Category:
Other

Cause:
The file does not exist for the request.

Action:
Ensure you are using the correct file name.

ESS-01312
Failed to close the output file for request {0}, file name {1}. {2}.

Category:
Other

Cause:
Failed to close the output file for the request.

Action:
Review the log file for runtime cause.

ESS-01313
Invalid directory for request {0}, directory {1}.

Category:
Other

Cause:
The directory is invalid for the request.

Action:
Ensure you are using the correct file name.

ESS-01314
Incompatible content operation for request {0}, content name {1}.

Category:
Other

Cause:
The operation is incompatible with the existing content type.

Action:
It is not allowed to export output content that was not imported. Updating existing output content using the API requires using the same content type.

ESS-01315
Error creating directory for request {0}, directory {1}.

Category:
Other

Cause:
Failed to create the request directory.

Action:
Ensure that RequestFileDirectory is configured correctly for the application and that the directory is writeable.

ESS-01316
Error exporting output content for request {0}, status {1}.

Category:
Other

Cause:
Failed to export output content to the request output directory.

Action:
Ensure that RequestFileDirectory is configured correctly for the application and that the directory is writeable. Check the log for errors.

ESS-01317
Error importing output content for request {0}, status {1}, directory {2}. {3}

Category:
Other

Cause:
Failed to import output files from the request output directory.

Action:
Check the log for errors.

ESS-01318
Failed to import the log for request {0}, log file {1}. {2}.

Category:
Other

Cause:
Failed to import the request log.

Action:
Review the log file for runtime cause.

ESS-01319
Invalid content handle mode for request {0}, content {1}.

Category:
Other

Cause:
The content handle is opened in the wrong mode for the operation being performed. The content must be opened in read for fetching and write for importing.

Action:
Re-open the content in the correct mode for the operation being performed.

ESS-01320
Invalid RequestFileDirectory {0} for application {1}.

Category:
Other

Cause:
The application has an invalid RequestFileDirectory configured.

Action:
Configure a valid RequestFileDirectory for the application.

ESS-01321
Error deleting files for request {0}, directory {1}.

Category:
Other

Cause:
Failed to delete files from the request work directory.

Action:
Manually delete the files from the file system.

ESS-01322
Error preserving log or output files for request {0}. {1}

Category:
Other

Cause:
Failed to preserve log or output files from the request work directory. This may be due to a problem with the directory or a previous version of the output file may already exist.

Action:
No action. The files have been removed.

ESS-01323
Invalid content open options for request {0} content category {1}, content name {2}.

Category:
Other

Cause:
The content open options are invalid.

Action:
Ensure that the content open options contain a single operation, and if applicable, options that are consistent with that operation.

ESS-01500
Dispatcher cannot be started while in {0} state.

Category:
Other

Cause:
Attempted to start the dispatcher when it is in a state for which the operation is not allowed.

Action:
Retry the operation when the dispatcher state is STOPPED.

ESS-01501
Dispatcher cannot be stopped while in {0} state.

Category:
Other

Cause:
Attempted to stop the dispatcher when it is in a state for which the operation is not allowed.

Action:
Retry the operation when the dispatcher state is STARTING or RUNNING.

ESS-01502
Processor cannot be started while in {0} state.

Category:
Other

Cause:
Attempted to start the processor when it is in a state for which the operation is not allowed.

Action:
Retry the operation when the processor state is STOPPED.

ESS-01503
Processor cannot be stopped while in {0} state.

Category:
Other

Cause:
Attempted to stop the processor when it is in a state for which the operation is not allowed.

Action:
Retry the operation when the processor state is STARTING or RUNNING.

ESS-01504
Cannot add endpoint {0} for application {1} because endpoint {2} already exists for application {3}.

Category:
Deployment

Cause:
The endpoint to add conflicts with an already existing endpoint.

Action:
Modify the endpoint name.

ESS-01505
Failed to retrieve information for request {0}.

Category:
Other

Cause:
Failed to retrieve runtime information for a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01506
Unable to create diagnostic incident. {0}

Category:
Other

Cause:
Failed to create diagnostic incident.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01507
Unable to register diagnostic dumps or rules. {0}

Category:
Other

Cause:
Failed to register diagnostic dumps or rules.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01508
Unable to unregister diagnostic dumps or rules. {0}

Category:
Other

Cause:
Failed to unregister diagnostic dumps or rules.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01509
Unable to create the diagnostic dump {0}. {1}

Category:
Other

Cause:
Failed to create the diagnostic dump.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01601
JobSet request {0} completed with an invalid final state {1}.

Category:
Other

Cause:
A JobSet request has been marked as completed, but has an unexpected final state.

Action:
Review the log file for errors pertaining to the request.

ESS-01602
First step is not defined in serial JobSet: {0}.

Category:
Other

Cause:
Cannot process a JobSet request due to invalid JobSet definition. The first step of a serial JobSet is not defined.

Action:
None

ESS-01603
Error dispatching subrequests for parent request {0}.

Category:
Other

Cause:
An error occurred while attempting to dispatch subrequests for a parent request in PAUSED state.

Action:
Review the log file to determine the nature of the problem.

ESS-01604
Failed to create {0} work unit for request {1}.

Category:
Other

Cause:
Unable to create the specified work unit for a request.

Action:
Review the log file to determine the nature of the problem.

ESS-01605
Failed to create event, {0}, for request {1}.

Category:
Other

Cause:
An error occurred while attempting to create an event for a request.

Action:
Review the log file to determine the nature of the problem.

ESS-01606
Failed to mark request {0} as completed.

Category:
Other

Cause:
An error prevented the request from being marked completed

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01607
Request {0} cannot be marked complete. State is {1}, process phase is {2}.

Category:
Other

Cause:
The request state and/or process phase prevents a request from being completed.

Action:
None

ESS-01608
Error occurred while processing request {0} by request dispatcher.

Category:
Other

Cause:
Failed to perform dispatch proccessing for the specified request.

Action:
Review the log file to determine the nature of the problem.

ESS-01700
Unrecognized request type : {0}.

Category:
Programmatic

Cause:
The job type used for the request is not supported.

Action:
Correct the job type definition.

ESS-01701
Unable to instantiate executable wrapper for execution type {0}.

Category:
Installation

Cause:
Unable to instantiate wrapper class used to process the request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01702
Unable to instantiate pre-process callback handler for request {0} using class name, {1}.

Category:
Programmatic

Cause:
Failed to instantiate an object for the pre-process callback handler class associated with a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01703
Unable to instantiate post-process callback handler for request {0} using class name, {1}.

Category:
Programmatic

Cause:
Failed to instantiate an object for the post-process callback handler class associated with a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01704
Error occurred at initiate stage during execution of request {0}. {1}

Category:
Programmatic

Cause:
An error occurred during the initiate stage of a request execution.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01705
Error occurred at finalize stage during execution of request {0}. {1}

Category:
Programmatic

Cause:
An error occurred during the finalize stage of a request execution.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01706
Invalid execution result code, {0}, for request {1}.

Category:
Programmatic

Cause:
A REQUEST_FINALIZATION event contained an unknown result code.

Action:
This indicates an internal error. Contact Oracle Support Services.

ESS-01707
Unable to instantiate Executable for Java request {0} using class name, {1}.

Category:
Programmatic

Cause:
Failed to instantiate Executable object for a Java request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01708
Database job for request {0} ended with error: {1}.

Category:
Programmatic

Cause:
Execution of a SQL request has ended with a error.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01709
Database job for request {0} ended with warning: {1}.

Category:
Programmatic

Cause:
Execution of a SQL request has ended with a warning.

Action:
None.

ESS-01710
Database job for request {0} was cancelled.

Category:
Programmatic

Cause:
Execution of a SQL request has been cancelled.

Action:
None.

ESS-01711
Database job for request {0} was paused. Paused state value: {1}.

Category:
Programmatic

Cause:
Execution of a SQL job request has been paused to allow one or more sub-requests to execute.

Action:
None. The execution of the paused request will be resumed once the sub-requests have completed.

ESS-01712
Failed to create database job for request {0}.

Category:
Other

Cause:
An error occurred trying to create an Oracle Scheduler job used to execute a SQL job request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01713
Error cancelling database job for request {0}.

Category:
Other

Cause:
An error occurred during post-execution clean tasks for an Oracle Scheduler job used to execute a SQL job request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01714
Database job for request {0} ended with business error: {1}.

Category:
Programmatic

Cause:
Execution of a SQL request has ended with a biz error.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01715
Failed to create database job for request {0} using Oracle Scheduler job class {1}.

Category:
Other

Cause:
An error occurred trying to create an Oracle Scheduler job used to execute a SQL job request with the given Oracle Scheduler job class.

Action:
Verify the EXECUTE privilege on the Oracle Scheduler job class has been granted to the ESS schema user. Review the log file for attached exceptions to determine the nature of the problem.

ESS-01716
Unable to process JobSet request {0}. JobSet definition has no steps: {1}

Category:
Programmatic

Cause:
The JobSet definition associated with a JobSet request has no steps.

Action:
Review the metadata of the JobSet definition for the specified metadata id.

ESS-01900
Error constructing ESS command {0}. {1}

Category:
Other

Cause:
An error is present in the command format.

Action:
Contact Oracle Support Services.

ESS-01901
Unsupported value, {0}, for attribute {1}.

Category:
Programmatic

Cause:
An unknown value was specified for a parameter.

Action:
Specify a valid attribute value.

ESS-01903
Unknown command type {0}. {1}

Category:
Other

Cause:
An unknown command type was submitted.

Action:
None

ESS-01904
Document is not valid for work {0}.

Category:
Other

Cause:
The command document is invalid for this Enterprise Scheduler server

Action:
None. The command will be deferred.

ESS-01905
Attribute {0} value {1} from command document does not match value {2} from command creation.

Category:
Other

Cause:
The internal command state is inconsistent for the given attribute.

Action:
Contact administrator.

ESS-01906
Error retrieving available command work.

Category:
Other

Cause:
Error occurred while retrieving command work to process.

Action:
Review the log file for runtime cause.

ESS-01907
Failed to access command work {0}.

Category:
Other

Cause:
Error occurred attempting to access command work.

Action:
Review the log file for runtime cause.

ESS-01908
Failed to update command work {0}.

Category:
Other

Cause:
Error occurred attempting to update command work.

Action:
Review the log file for runtime cause.

ESS-01909
Failed to delete command work {0}.

Category:
Other

Cause:
Error occurred attempting to delete command work.

Action:
Review the log file for runtime cause.

ESS-01910
Failed to delete command work for request {0}.

Category:
Other

Cause:
Error occurred attempting to delete command work for a request.

Action:
Review the log file for runtime cause.

ESS-01911
Failed to check in command work {0}.

Category:
Other

Cause:
Error occurred attempting to check in command work.

Action:
Review the log file for runtime cause.

ESS-01912
Failed to check in command work for instance {0}.

Category:
Other

Cause:
Error occurred attempting to check in command work for an instance.

Action:
Review the log file for runtime cause.

ESS-01913
Command work not found: {0}.

Category:
Other

Cause:
The specified command work was not found.

Action:
None

ESS-01914
Command work {0} is not checked out to instance {1}.

Category:
Other

Cause:
The command work is not checked out to a specific instance.

Action:
None

ESS-01915
Failed to lock command work {0} by instance {1}.

Category:
Other

Cause:
Failed to lock the command work by the specified instance.

Action:
None

ESS-01970
Error during request purge processing.

Category:
Other

Cause:
An error was encountered during purge of request data.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01971
Error while purging request data from table {0} for request {1}.

Category:
Other

Cause:
An error was encountered during purge of request data from the specified table.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01972
Error during request purge processing for session {0}.

Category:
Other

Cause:
An error was encountered during purge of request data.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01973
Error while purging request data from table {0} for session {1}.

Category:
Other

Cause:
An error was encountered during purge of request data from the specified table.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01974
Error while purging request data from table {0} for request {1}, session {2}.

Category:
Other

Cause:
An error was encountered during purge of request data from the specified table.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01980
Batch delete initialization failed.

Category:
Other

Cause:
An error occurred during initialization of batch delete support.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01981
Failed to delete request {0}. Reason: {1}

Category:
Other

Cause:
An error occurred attempting to delete a request.

Action:
None

ESS-01982
Insufficient privileges to delete request {0}.

Category:
Other

Cause:
Execution user of a batch delete job does not have sufficient privileges to delete the request.

Action:
Batch delete job should be submitted only by ESS administrator

ESS-01983
Error determining requests for batch delete.

Category:
Other

Cause:
An error occurred attempting to determine requests to delete.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01984
Error occurred while executing batch delete request {0}. Cause: {1}

Category:
Other

Cause:
An error occurred during request execution.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01985
Execution of request {0} was cancelled.

Category:
Other

Cause:
Request execution was canceled.

Action:
None

ESS-01987
Runtime store error during batch delete.

Category:
Other

Cause:
Runtime store error occurred during batch delete operation.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01988
Failed to lock request for batch delete.

Category:
Other

Cause:
Unable to lock one or more requests during batch delete operation

Action:
None

ESS-01989
Batch delete request {0} failed to delete request {1}. Reason: {2}

Category:
Other

Cause:
Batch delete job failed to delete the specified request.

Action:
Review log file to determine the reason.

ESS-01995
Failed to create delete session.

Category:
Other

Cause:
Failed to initialize delete session used for request data delete or purge.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01996
Failed to lock delete session table.

Category:
Other

Cause:
Failed to lock delete session table used for request data delete or purge.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01997
Failed to access delete session information.

Category:
Other

Cause:
Failed to access delete session information used for request data delete or purge.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-01998
Runtime store operation failed for delete session {0}.

Category:
Other

Cause:
Runtime store error occurred during delete session operation.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-02001
User {0} does not have execute permission on metadata object {1}. Request {2} execution is aborted.

Category:
Other

Cause:
User {0} does not have execute permission on metadata object {1}. Request {2} execution is aborted.

Action:
Check the policy assignment..

ESS-02002
User {0} does not have sufficient privilege to perform operation {1}.

Category:
Other

Cause:
User {0} does not have sufficient privilege to perform operation {1}.

Action:
Grant the policy to the user {0}..

ESS-02003
User {0} does not have sufficient privilege to perform operation {1} on request {2}.

Category:
Other

Cause:
User {0} does not have sufficient privilege to perform operation {1} on request {2}.

Action:
Grant the policy to the user {0}..

ESS-02004
User or appid {0} is not a valid entry in the identity store.

Category:
Other

Cause:
{0} can not be authenticated.

Action:
Check the user settting.

ESS-02005
User {0} does not have {1} privilege on metadata object {2}. Request {3} validation failed.

Category:
Other

Cause:
User {0} does not have {1} privilege on metadata object {2}. Request {3} validation failed.

Action:
Check the policy assignment..

ESS-02006
User {0} does not have sufficient privilege to perform operation {1} on job set {2}, failed steps are {3}.

Category:
Other

Cause:
User {0} does not have sufficient privilege to perform operation {1} on jobset {2}, failed steps are {3}.

Action:
Grant the policy to the user {0}..

ESS-02007
User or appid {0} that job {1} runs as is not a valid entry in the identity store.

Category:
Other

Cause:
The user or appid {0} is not a valid identity or can not be authenticated.

Action:
Check your metadata definition.

ESS-02008
Invalid value {0} specified for FADataSecurityPolicyOverrides property in ess-config. Continuing permission checks using default FND policy.

Category:
Other

Cause:
Invalid value specified for FADataSecurityPolicyOverrides property in ess-config

Action:
Use a supported value.

ESS-02200
Mismatched request handles for request {0}.

Category:
Other

Cause:
The request may have been retried.

Action:
Update with request execution context from new execution if desired.

ESS-02220
Failed to deliver web service callback for message {0} for request {1}.

Category:
Other

Cause:
The web service asynchronous callback message could not be delivered.

Action:
The action may be retried. Check the log files.

ESS-02221
Invalid web service request message {0} for getCompletionStatus operation.

Category:
Other

Cause:
The web service request to getCompletionStatus was invalid.

Action:
Check the attached exceptions and fix the web service request.

ESS-03000
Metadata name cannot contain character '/'

Category:
Other

Cause:
Invalid metdata type name

Action:
Provide a valid metadata name

ESS-03001
Both explicit date and recurrence cannot be null.

Category:
Other

Cause:
Both explicit date and recurrence cannot be null.

Action:
Provide explicit date or recurrence.

ESS-03002
ExclusionDefinition must contain at least one exclusion

Category:
Other

Cause:
ExclusionDefinition is empty

Action:
Include atleast one exclusion in ExclusionDefinition.

ESS-03003
Incompatibility already has an entity for job definition:{0}

Category:
Other

Cause:
Incompatibility already has the corresponding job definition.

Action:
Don't add the job definition to the Incompatibility.

ESS-03004
Incompatibility defined for a single entity must be self-incompatible on that entity.

Category:
Other

Cause:
Incompatibility defined for a single entity must be self-incompatible on that entity

Action:
A valid incompatibility definition must have at least two entities or one self-incompatible entity

ESS-03005
Identifier not specified for incompatibility entity.

Category:
Other

Cause:
Identifier not specified for incompatibility entity.

Action:
Specify identifier for incompatibility entity.

ESS-03006
Property not specified for an entity of a {0} incompatibility

Category:
Other

Cause:
Property not specified for Incompatibility entity.

Action:
Specify property for Incompatibility entity.

ESS-03007
Property {0} is defined as read-only in the JobType definition.

Category:
Other

Cause:
Read-only property is defined in JobType definition

Action:
Make sure that no read-only property is specified for Jobtype Definition.

ESS-03008
Unable to convert steps to XML Document

Category:
Other

Cause:
Conversion of JobSet's JobSetStep objects to an XML Document failed

Action:
Internal error

ESS-03009
Failed to validate Jobset/JobsetSteps document against the schema :{0}

Category:
Other

Cause:
Failed to validate Jobset/JobsetSteps document against the schema

Action:
Internal error

ESS-03010
Unable to convert XML steps to objects

Category:
Other

Cause:
Unable to convert XML steps to objects

Action:
Internal error

ESS-03011
First step must be defined for serial job set.

Category:
Other

Cause:
Jobset has steps, but the first step is not defined.

Action:
First step must be defined for serial jobset.

ESS-03012
First step id does not specify a defined step:{0}

Category:
Other

Cause:
First step id of Jobset does not specify a defined step

Action:
First step must be a defined one for serial jobset.

ESS-03013
Invalid link step id for {0}

Category:
Other

Cause:
Invalid link step id

Action:
Check that step links are valid step ids..

ESS-03014
Jobset has no steps.

Category:
Other

Cause:
Jobset has no steps

Action:
Ensure Jobset have steps

ESS-03015
Invalid Serial JobSet:loops are not allowed. See step {0}

Category:
Other

Cause:
Invalid Serial JobSet:loops are not allowed

Action:
Avoid loops in serial Jobset

ESS-03016
Step already exists:{0}

Category:
Other

Cause:
Step already exists in Jobset

Action:
Avoid adding duplicate step

ESS-03017
Can"t define Procedure Name, or CmdLine for a Java JobType definition

Category:
Other

Cause:
Cannot define Procedure Name, or CmdLine for a Java JobType definition

Action:
Java job type cannot have properties of SQL or PROCESS Job Type.

ESS-03018
Can"t define Class Name, CmdLine, or for a SQL JobType definition

Category:
Other

Cause:
Cannot define Class Name, CmdLine for a SQL JobType definition

Action:
Procedure name can be defined for SQL JobType.

ESS-03019
Can"t define Class Name or Procedure name for a Binary JobType definition

Category:
Other

Cause:
Cannot define Class Name or Procedure name for a Process JobType definition

Action:
CmdLine supported for Process JobType.

ESS-03020
Both FREQUENCY and ICAL Expression cannot be null

Category:
Other

Cause:
Both FREQUENCY and ICAL Expression cannot be null

Action:
Specify either Frequency or Ical expression.

ESS-03021
Cannot have start date after end date

Category:
Other

Cause:
Cannot have start date after end date

Action:
Correct the start or end date

ESS-03022
Cannot specify Recurrence Fields WEEK_OF_MONTH without DAY_OF_WEEK

Category:
Other

Cause:
Cannot specify recurrence fields WEEK_OF_MONTH without DAY_OF_WEEK

Action:
Given weeks of month, days of week is must.

ESS-03023
Cannot specify MONTH_OF_YEAR for MONTHLY frequency. MONTH_OF_YEAR can be specified for YEARLY frequency.

Category:
Other

Cause:
Cannot specify recurrence fields MONTH_OF_YEAR for MONTHLY frequency.

Action:
Month of year can be specified for yearly frequency.

ESS-03024
Cannot specify MONTH_OF_YEAR, WEEK_OF_MONTH or DAY_OF_MONTH for WEEKLY frequency

Category:
Other

Cause:
Cannot specify recurrence fields MONTH_OF_YEAR, WEEK_OF_MONTH or DAY_OF_MONTH for WEEKLY frequency

Action:
Other fields cannot have bigger scope then frequency

ESS-03025
Only TIME_OF_DAY field can be specified with DAILY frequency

Category:
Other

Cause:
Only time of day field can be specified with daily frequency.

Action:
Only time of day field can be specified with daily frequency.

ESS-03026
RecurrenceFields cannot be specified with 'HOURLY', 'MINUTELY' or 'SECONDLY' frequency

Category:
Other

Cause:
Recurrence fields cannot be specified with HOURLY, MINUTELY or SECONDLY frequency

Action:
Recurrence fields cannot be specified with HOURLY, MINUTELY or SECONDLY frequency

ESS-03027
RecurrenceFields have invalid Month, Date combinations.

Category:
Other

Cause:
Recurrence fields have invalid Month, Date combinations.

Action:
Specify correct month, date combinations.

ESS-03028
RecurrenceSet can"t have more than {0} recurrences

Category:
Other

Cause:
RecurrenceSet cannot have more than 5 recurrences

Action:
Reduce the number of recurrences

ESS-03029
Event filters should have no more than one operator

Category:
Other

Cause:
Event filters have more than one operator.

Action:
Correct Event filters to have no more than one operator.

ESS-03030
{0} and {1} are the only supported fields for event filters

Category:
Other

Cause:
EventType and EventName are the only supported fields for event filters.

Action:
EventType and EventName are the only supported fields for event filters.

ESS-03031
Work Assignment must specify at least one Workshift

Category:
Other

Cause:
Work Assignment has no Workshift.

Action:
Work Assignment must specify at least one Workshift.

ESS-03033
Illegal value provided for Actions in parameter

Category:
Other

Cause:
Illegal value provided for Metadata permission actions in parameter.

Action:
Illegal value provided for Metadata permission actions in parameter.

ESS-03034
MetadataPermissionStrings parameter cannot be null.

Category:
Other

Cause:
MetadataPermissionStrings parameter cannot be null or empty.

Action:
Specify non-empty metadata permission strings

ESS-03035
Actions parameter cannot be null.

Category:
Other

Cause:
Actions parameter cannot be null or empty.

Action:
Actions parameter cannot be null or empty.

ESS-03036
Failed to commit changes and close service handle. Referential Integrity violation detected. Referencing objects exist for the object(s) being deleted.

Category:
Other

Cause:
Deletion of object not possible as it is referenced by some other object

Action:
Check the dependent objects before deletion.

ESS-03037
Invalid options due to missing operation: {0}

Category:
Other

Cause:
Invalid options.

Action:
Provide valid options.

ESS-03038
Invalid options for Read operation: {0}

Category:
Other

Cause:
Invalid options for Read operation.

Action:
Specify correct options for read operation.

ESS-03039
Invalid options for Write operation: {0}

Category:
Other

Cause:
Invalid options for Write operation.

Action:
Specify correct options for write operation.

ESS-03040
Invalid options for Import operation: {0}

Category:
Other

Cause:
Invalid options for Import operation.

Action:
Specify correct options for import operation

ESS-03041
Invalid options for Log content: {0}

Category:
Other

Cause:
Invalid options for Log content.

Action:
Specify correct options for log content.

ESS-03042
Definition is required

Category:
Other

Cause:
Job or jobset definition Id is missing

Action:
Job or jobset definition Id is required

ESS-03043
Incompatibility definition, {0}, from runtime store is {1} incompatibility type. Expected type is {2}

Category:
Other

Cause:
Incompatibility type mismatch between metadata store and runtime store for the request

Action:
There should be no mismatch. Internal error

ESS-03044
Incompatibility definition, {0},from runtime store does not contain an entity for {1}

Category:
Other

Cause:
Incompatibility definition from runtime store does not contain an entity for Job/Jobset

Action:
Entity must be present in Incompatibility definition. Internal error.

ESS-03045
Map parameter cannot be null.

Category:
Other

Cause:
Config properties map is null

Action:
Config properties map cannot be null

ESS-03046
Application parameter cannot be null.

Category:
Other

Cause:
Application parameter provided to fetch config properties is null

Action:
Provide non null application name.

ESS-03047
PropertyType enum cannot be null.

Category:
Other

Cause:
PropertyType enum is null.

Action:
PropertyType enum cannot be null.

ESS-03048
PropertyName parameter cannot be null.

Category:
Other

Cause:
PropertyName parameter is null.

Action:
PropertyName parameter cannot be null.

ESS-03049
PropertyValue parameter cannot be null.

Category:
Other

Cause:
PropertyValue parameter is null.

Action:
PropertyValue parameter cannot be null.

ESS-03050
Trigger definition cannot be null.

Category:
Other

Cause:
Trigger definition is null.

Action:
Trigger definition cannot be null.

ESS-03051
No specialization in configured bindings for {0}

Category:
Other

Cause:
No specialization in configured bindings.

Action:
Specify specialization in configured bindings.

ESS-03052
{0} is not bound on this instance

Category:
Other

Cause:
Work Assignment not bound on this instance.

Action:
Work Assignment not bound on this instance.

ESS-03053
Request parameters cannot be null.

Category:
Other

Cause:
Request parameters are null.

Action:
Request parameters cannot be null.

ESS-03054
Illegal value provided for Actions in parameter.

Category:
Other

Cause:
Illegal value provided for Actions in parameter.

Action:
Provide proper values for Actions in parameter.

ESS-03055
Invalid binding mode: name={0},exclusiveMode={1}

Category:
Other

Cause:
Invalid binding mode.

Action:
Invalid binding mode.

ESS-03056
Filter parameters with DATETIME datatype are not supported

Category:
Other

Cause:
Filter parameters with DATETIME datatype are not supported.

Action:
DATETIME datatype cannot be used with Filter parameters

ESS-03058
Value of deltaStart or deltaEnd cannot be negative

Category:
Other

Cause:
Value of deltaStart or deltaEnd is negative.

Action:
Value of deltaStart or deltaEnd cannot be negative

ESS-03059
Datatype is not supported for a parameter value:{0}

Category:
Other

Cause:
Unsupported datatype for parameter.

Action:
Unsupported datatype for parameter.

ESS-03060
Failed to convert parameter value to data type:{0}

Category:
Other

Cause:
Failed to convert parameter value to data type.

Action:
Failed to convert parameter value to data type.

ESS-03061
Value of parameter {0} has data type {1} instead of the expected data type {2}

Category:
Other

Cause:
Parameter value datatype mismatch.

Action:
Parameter value datatype mismatch.

ESS-03062
Step must be JobDefinition or JobSet

Category:
Other

Cause:
Invalid step type.

Action:
Step must be JobDefinition or JobSet.

ESS-03063
Unknown data type for parameter {0}

Category:
Other

Cause:
Unknown datatype for parameter.

Action:
Unknown datatype for parameter.

ESS-03064
Operation not supported for scoped parameter {0}

Category:
Other

Cause:
Operation not supported for scoped parameter.

Action:
Operation not supported for scoped parameter.

ESS-03065
RecurrenceSet must contain at least one recurrence

Category:
Other

Cause:
RecurrenceSet is empty.

Action:
RecurrenceSet must contain atleast one recurrence.

ESS-03066
Unable to delete workshift {0} that is referenced by a work assignment.

Category:
Other

Cause:
Wokshift deletion failed as it is referenced by a work assignment

Action:
Ensure that workshift is not referenced in a work assignment before deletion

ESS-03067
Unable to delete schedule {0} that is referenced by a workshift.

Category:
Other

Cause:
Schedule deletion failed as it is referenced by a work shift

Action:
Ensure that schedule is not referenced by a work shift before deletion

ESS-05000
Error occurred. {0}

Category:
Other

Cause:
Enterprise Scheduler Service encountered an error.

Action:
Review the log file for indications of the problem.

ESS-05010
Request {0} not found.

Category:
Other

Cause:
Request with the given request id can not be found in the database.

Action:
None

ESS-05011
Request {0} set to {1} state.

Category:
Other

Cause:

Action:

ESS-05012
Request {0} set to {2} state. Previous state was {1}.

Category:
Other

Cause:

Action:

ESS-05013
Request {0}. Process phase {1} not in valid phases {2}.

Category:
Other

Cause:
The process phase of the request is inconsistent with its current status.

Action:
None

ESS-05015
Oracle Enterprise Scheduler. Release Version: {0}, Build: {1}

Category:
Other

Cause:
Information about release version and build label of Oracle Enterprise Scheduler.

Action:
No action is necessary.

ESS-05016
Oracle Enterprise Scheduler runtime store. Schema Name: {0}, Version: {1}, Status: {2}

Category:
Other

Cause:
Information about the runtime store used by Oracle Enterprise Scheduler.

Action:
No action is necessary.

ESS-05021
Failed to begin transaction.

Category:
Other

Cause:
Being of a user transaction failed.

Action:
Review the log file for runtime cause.

ESS-05022
Failed to commit transaction.

Category:
Other

Cause:
Failed to commit the transaction.

Action:
Review the log file for runtime cause.

ESS-05023
Failed to rollback transaction.

Category:
Other

Cause:
Failed to rollback the transaction.

Action:
Review the log file for runtime cause.

ESS-05024
Failed to set transaction timeout.

Category:
Other

Cause:
Failed to set transaction timeout.

Action:
Review the log file for runtime cause.

ESS-05025
Error in transaction processing. The transaction is eligible to be retried.

Category:
Other

Cause:
A recoverable SQL error was encountered

Action:
None

ESS-05038
Failed to find JNDI resource for {0}.

Category:
Configuration

Cause:
Failed to perform a JNDI lookup for a given resource name.

Action:
Verify the configuration for the resource.

ESS-05039
Error occurred closing JNDI naming context.

Category:
Other

Cause:
An error occurred while trying to close a JNDI naming context.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05043
Failed to commit SQL transaction.

Category:
Other

Cause:
An error occurred trying to commit database transaction.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05044
Failed to rollback SQL transaction.

Category:
Other

Cause:
An error occurred trying to rollback database transaction.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05045
Error using SQL ResultSet. {0}

Category:
Other

Cause:
An error occurred while using an SQL ResultSet.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05046
Failed to close an SQL ResultSet.

Category:
Other

Cause:
An error occurred trying to close an SQL ResultSet.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05047
Failed to close an SQL Statement.

Category:
Other

Cause:
An error occurred trying to close an SQL Statement.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05048
Failed to obtain a database connection.

Category:
Other

Cause:
An error occurred trying to obtain a database connection.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05049
Failed to close a database connection.

Category:
Other

Cause:
An error occurred trying to close a database connection.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05053
Failed to map object of type {0} to CompositeData.

Category:
Other

Cause:
An error occurred converting an ESS object to a javax.management.openmbean.CompositeData object

Action:
Contact Oracle Support Services

ESS-05054
Failed to map CompositeData object to {0}.

Category:
Other

Cause:
An error occurred converting a javax.management.openmbean.CompositeData object to an ESS object

Action:
Contact Oracle Support Services

ESS-05055
Illegal state transition from {0} to {1} for request {2}.

Category:
Other

Cause:
An update event's timing may have tried to change the state after the request has begun a transition to a terminal state.

Action:
This warning can be ignored.

ESS-05100
Operator {1} is invalid with query field {0}. Valid operators are: {2}.

Category:
Other

Cause:
Operator is invalid for the given query field.

Action:
Use a valid operator.

ESS-05101
Comparator {1} is invalid with query field {0}. Valid comparators are: {2}.

Category:
Other

Cause:
Comparator is invalid for the given query field.

Action:
Use a valid comparator.

ESS-05102
Value of type {1} is invalid with query field {0}. Valid value types are: {2}.

Category:
Other

Cause:
Value type is invalid for the given query field.

Action:
Use a valid value type.

ESS-05103
Value of type null is invalid with query field {0}.

Category:
Other

Cause:
Null value type is invalid for the given query field.

Action:
Use a valid non-null value type.

ESS-05104
Failed to check in {0} work unit {1} for request {2}. {3}

Category:
Other

Cause:
The work unit for the given request could not be checked in or deleted.

Action:
The work unit operation should be automatically retried, so no action is necessary.

ESS-05105
Metadata of type {0} cannot be customized. Only metadata of the following types can be customized: {1}.

Category:
Other

Cause:
An invalid metadata type was provided.

Action:
Provide a valid customizable metadata type.

ESS-05106
Property {0} cannot be assigned a value of type {1}. Values for property {0} can only have the following types: {2}.

Category:
Other

Cause:
The data type of the provided property is not valid.

Action:
Provide a value with the correct data type.

ESS-05107
An error occurred while parsing the metadata object id string: {0}

Category:
Other

Cause:
An error occurred while parsing a metadata object id string.

Action:
See base exception for detailed underlying cause.

ESS-05108
The user provided metadata type of {0} does not match the metadata type of {1} in the metadata object id string

Category:
Other

Cause:
The metadata type specified by the user does not match the metadata type specified by the metadata object id string.

Action:
Check the metadata repository to ensure the metadata is correct or specify the correct type and try again.

ESS-05109
While performing a metadata query, the following problem was detected with one of the query results: {1} The query will continue but exclude the piece of metadata with name {0}. This may affect the expected query results.

Category:
Other

Cause:
A problem occurred while processing a result of the metadata query.

Action:
Check the piece of metadata causing the problem for any issues and check the health of the metadata respository.

ESS-05110
An error occurred while retrieving the metadata object with name {0} of type {1}.

Category:
Other

Cause:
A problem occurred while retrieving a piece of metadata.

Action:
See the base exception for the cause then check the piece of metadata causing the problem for any issues and check the health of the metadata respository.

ESS-05111
Bulk metadata customization input file {0} does not exist or is not readable.

Category:
Other

Cause:
Invalid XML input file specified for bulk customization.

Action:
Provide the correct input XML file for bulk customization.

ESS-05112
Bulk metadata customization output file {0} is not writable.

Category:
Other

Cause:
Invalid XML output file specified for bulk customization.

Action:
Provide the correct output XML file absolute pathname.

ESS-05113
Argument type is not supported: {0}

Category:
Other

Cause:
The type of argument is unsupported.

Action:
Use a supported argument type.

ESS-05114
Failed to check in {0} work unit {1}. {2}

Category:
Other

Cause:
The work unit could not be checked in or deleted.

Action:
The work unit operation should be automatically retried, so no action is necessary.

ESS-05202
ESS connections.xml {0} property lookup returns null. Please verify adf-domain-config for ESS is set up and configured.

Category:
Other

Cause:
ESS connections.xml property lookup returns NULL.

Action:
Verify adf-domain-config for ESS is set up and configured.

ESS-05203
ESS connections.xml {0} property lookup returns Unresolved EL Expression. Please verify adf-domain-config for ESS is set up and configured.

Category:
Other

Cause:
ESS connections.xml property lookup returns Unresolved EL Expression.

Action:
Verify adf-domain-config for ESS is set up and configured.

ESS-05204
NamingException looking up EssConnection {0}.

Category:
Other

Cause:
NamingException looking up EssConnection.

Action:
Review the log file for attached exceptions to determine the cause.

ESS-05205
Error reading EssConnection Tokens from adf-domain-config.

Category:
Other

Cause:
Error reading EssConnection Tokens from adf-domain-config.

Action:
Review the log file for attached exceptions to determine the cause.

ESS-05206
Error writing EssConnection Tokens to adf-domain-config.

Category:
Other

Cause:
Error writing EssConnection Tokens to adf-domain-config.

Action:
Review the log file for attached exceptions to determine the cause.

ESS-05490
Service MBeans registration failed.

Category:
Other

Cause:
Service MBeans registration failed.

Action:
Review the log file for underlying causes.

ESS-05700
Failed to obtain a metadata service instance. {0}

Category:
Other

Cause:
Failed to obtain a metadata service instance.

Action:
Review the log file for underlying causes.

ESS-05704
An error occurred invoking the MetadataService MBean. {0}

Category:
Programmatic

Cause:
An error occurred invoking the RuntimeService MBean.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05705
Failed to save the {0} with name {1} in application {2}.

Category:
Programmatic

Cause:
Failed to save the metadata object.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05706
{0} with name {1} does not exist in application {2}.

Category:
Programmatic

Cause:
Unable to find the metadata object.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05707
{0} with name {1} already exists in application {2}.

Category:
Programmatic

Cause:
The metadata object already exists.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05708
Failed to delete the {0} with name {1} in application {2}.

Category:
Programmatic

Cause:
Unable to delete the metadata object

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-05709
Metadata parameter {0} starts with {1} which is a reserved parameter keyword.

Category:
Programmatic

Cause:
A property defined by the metadata object contains a reserved keyword.

Action:
Remove the reserved keyword from the property name.

ESS-05710
A validation error occurred while validating JobSet step {0}.

Category:
Programmatic

Cause:
A JobSet step failed validation.

Action:
See the base validation exception for the original validation error.

ESS-05711
A null value cannot be used when querying the {0} field.

Category:
Other

Cause:
A value of null was used as the query value.

Action:
Provide a non-null argument.

ESS-05712
The metadata object with id {0} cannot be deleted because it belongs to one of the following restricted packages: {1}. However, metadata in the custom namespace, {2}, can be deleted.

Category:
Programmatic

Cause:
The metadata object to be deleted resides in a read-only package.

Action:
This metadata object cannot be deleted by end users.

ESS-05713
The metadata object with id {0} cannot be updated because it belongs to one of the following restricted packages: {1}. However, metadata in the customer namespace, {2}, can be updated.

Category:
Programmatic

Cause:
The metadata object to be updated resides in a read-only package.

Action:
This metadata object cannot be updated by end users.

ESS-05714
The metadata object with id {0} cannot be customized. Only metadata in the following packages can be customized: {1}. However, metadata in the customer namespace, {2}, cannot be customized.

Category:
Programmatic

Cause:
The metadata object to be customized does not reside in a package that allows customization.

Action:
This metadata object cannot be customized by end users.

ESS-05715
Metadata parameter {0} cannot have value {1} because {1} is a reserved value.

Category:
Programmatic

Cause:
The value of a property defined by the metadata object contains a reserved keyword.

Action:
Change the value of the property.

ESS-05716
Metadata parameter {0} cannot have an empty or null value.

Category:
Programmatic

Cause:
The value of a property defined by the metadata object was empty or null.

Action:
Change the value of the property.

ESS-06000
Failed to obtain a runtime service instance. {0}

Category:
Other

Cause:
Failed to obtain a runtime service instance.

Action:
Review log file for underlying cause.

ESS-06002
Failed to close runtime service handle. {0}

Category:
Other

Cause:
Failed to close runtime service handle.

Action:
Review the log file for underlying causes.

ESS-06003
Runtime service system failure. {0}

Category:
Other

Cause:
Runtime service system failure.

Action:
Review the log file for underlying causes.

ESS-06100
No request found for the given id {0}.

Category:
Programmatic

Cause:
A request was not found in ESS runtime storage corresponding to the indicated request identifier.

Action:
Specify a request identifier for an existing request.

ESS-06102
An error occurred invoking the RuntimeService MBean.

Category:
Other

Cause:
An error occurred invoking the RuntimeService MBean.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06500
Starting ESS resource adapter.

Category:
Other

Cause:

Action:

ESS-06501
Stopping ESS resource adapter.

Category:
Other

Cause:

Action:

ESS-06502
Endpoint activation for {0}.

Category:
Other

Cause:

Action:

ESS-06503
Endpoint deactivation for {0}.

Category:
Other

Cause:

Action:

ESS-06510
Registering application, {0}, via ClassLoader: {1}

Category:
Other

Cause:

Action:

ESS-06511
Registered application: {0} adfConfigUrl: {1} connUrl: {2}

Category:
Other

Cause:

Action:

ESS-06512
Removed registered configuration for application {0}.

Category:
Other

Cause:

Action:

ESS-06514
Application {0} is already registered.

Category:
Other

Cause:

Action:

ESS-06515
The logical name of this application, {0}, is already in use by the following deployed applications (possibly in different domains): {1}.

Category:
Other

Cause:
The logical name of this application is already in use by other applications using a different deployed name as this application.

Action:
If this is the same application as one of the above applications then its deployed name should be changed to match. Otherwise, select a unique logical name for this application.

ESS-06516
The deployed name of this application, {0}, is already in use by the following logical applications (possibly in different domains): {1}.

Category:
Other

Cause:
The deployed name of the application is already in use by other applications using a different logical name as this application.

Action:
If this is the same application as one of the above applications then its logical name should be changed to match. Otherwise, select a unique deployed name for this application.

ESS-06517
Logical application name {0} is a reserved keyword.

Category:
Other

Cause:
The specified logical application name is a reserved keyword.

Action:
Change the name of the logical application.

ESS-06521
Failed to start request dispatcher.

Category:
Other

Cause:
An error occurred while trying to start the request dispatcher.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06522
Failed to start request processor.

Category:
Other

Cause:
An error occurred while trying to start the request processor.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06523
Failed to start system event service.

Category:
Other

Cause:
An error occurred while trying to start the system event service.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06524
Failed to start application event service.

Category:
Other

Cause:
An error occurred while trying to start the application event service.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06525
Failed to start heartbeat monitor.

Category:
Other

Cause:
An error occurred while trying to start the heartbeat monitor.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06526
Failed to update configuration information.

Category:
Other

Cause:
An error occurred while trying to update configuration information.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06527
Failed to start deferred monitor.

Category:
Other

Cause:
An error occurred while trying to start the deferred monitor.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06528
Failed to start work unit worker.

Category:
Other

Cause:
An error occurred while trying to start the work unit worker.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06529
Failed to start change event service.

Category:
Other

Cause:
An error occurred while trying to start the change event service.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06530
Dispatcher cannot be started when it is in the {0} state.

Category:
Other

Cause:
Dispatcher cannot be started when it is in the specified state.

Action:
Start the dispatcher when it is in STOPPED state.

ESS-06531
Dispatcher cannot be stopped when it is in the {0} state.

Category:
Other

Cause:
Dispatcher cannot be stopped when it is in the specified state.

Action:
Stop the dispatcher when it is in STARTING or RUNNING state.

ESS-06532
Processor cannot be started when it is in the {0} state.

Category:
Other

Cause:
Processor cannot be started when it is in the specified state.

Action:
Start the processor when it is in STOPPED state.

ESS-06533
Processor cannot be stopped when it is in the {0} state.

Category:
Other

Cause:
Processor cannot be stopped when it is in the specified state.

Action:
Stop the processor when it is in STARTING or RUNNING state.

ESS-06534
{0} is an unversioned ESS hosting application. Unversioned hosting applications are deprecated and will not be supported in subsequent releases. Some features are only supported for versioned applications.

Category:
Other

Cause:
The ESS hosting application does is not versioned.

Action:
Make the application versioned or expect certain features not to work.

ESS-06538
No endpoint is available for {0}.

Category:
Other

Cause:
An application using the specified endpoint application name is not deployed.

Action:
Review the log file for underlying causes.

ESS-06539
Could not create endpoint for {0}.

Category:
Other

Cause:
An error occurred creating an application endpoint.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06540
Failed to get an endpoint to run dispatcher for application {0}.

Category:
Other

Cause:
Dispatch monitor was unable to obtain an application endpoint. This may happen when the system is busy and does not necessary indicate a problem.

Action:
Review the log file for indications of a problem if this persists.

ESS-06541
Error during dispatch for application {0}.

Category:
Other

Cause:
Error during dispatch for application.

Action:
Review the log for underlying causes.

ESS-06542
Error getting applications to dispatch.

Category:
Other

Cause:
Error getting applications for dispatch.

Action:
Review the log for underlying causes.

ESS-06543
Failed to deactivate endpoint for application {0}.

Category:
Other

Cause:
An error occurred while removing an application endpoint.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06557
Failed to start heartbeat worker {0}.

Category:
Other

Cause:
ESS heart beat monitor failed to start due to a system failure.

Action:
Check the causeBy clause of this exception to find more details.

ESS-06558
Failed to get an endpoint to run a heartbeat for application {0}.

Category:
Other

Cause:
Heartbeat monitor was unable to obtain an application endpoint. This may happen when the system is busy and does not necessary indicate a problem.

Action:
Review the log file for indications of a problem if this persists.

ESS-06560
Error encountered by event worker.

Category:
Other

Cause:
Error encountered by event worker.

Action:
Review the log for underlying causes.

ESS-06570
Failed to get metadata for work assignment {0}.

Category:
Other

Cause:
Unable to retrieve work assignment metadata when analyzing work assignment bindings. The work assignment is ignored.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06571
Failed to get workshift metadata ({0}) for work assignment {1}.

Category:
Other

Cause:
Unable to retrieve workshift metadata when analyzing a work assignment binding. The work assignment processing will ignore the workshift.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06572
Failed to get schedule metadata ({0}) for work assignment {1}.

Category:
Other

Cause:
Unable to retrieve schedule metadata when analyzing a work assignment binding. The work assignment processing will ignore the workshift associated with the schedule.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06573
Failed to start work assignment {0}.

Category:
Other

Cause:
Unable to start the first worker for the work assignment. The start will be retried in a short time.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06574
Failed to start starvation thread for work assignment {0}.

Category:
Other

Cause:
Unable to start the starvation worker for the work assignment. The work assignment will be activated without the starvation worker.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06575
Skipping inactive work assignment {0}.

Category:
Other

Cause:
The work assignment is defined as inactive and is being skipped.

Action:
If the work assignment should be active, change it to active and reload work assignment metadata.

ESS-06576
Binding default work assignment.

Category:
Other

Cause:
The default work assignment is being bound because no user-defined work assignments were bound.

Action:
No action is necessary.

ESS-06577
Skipping inactive workshift {0} for work assignment {1}.

Category:
Other

Cause:
The workshift is being skipped because it is inactive. It may have an allocation of 0 or a duration of 0.

Action:
No action is necessary.

ESS-06578
Started work assignment {0}.

Category:
Other

Cause:
Started the work assignment.

Action:
No action is necessary.

ESS-06579
Stopped work assignment {0}.

Category:
Other

Cause:
Stopped the work assignment.

Action:
No action is necessary.

ESS-06580
Skipping invalid work assignment {0}.

Category:
Other

Cause:
The work assignment is being ignored because it is invalid.

Action:
Check the work assignment and correct the problem. Ensure the work assignment has at least one workshift defined.

ESS-06581
Skipping invalid work assignment binding {0}.

Category:
Other

Cause:
The work assignment is being ignored because the binding is invalid.

Action:
Check the work assignment binding mode and correct the problem.

ESS-06582
Skipping completed work assignment {0}.

Category:
Other

Cause:
The work assignment has completed and will never again become active. It is being skipped.

Action:
If the work assignment should not be completed, check the workshift schedules to ensure they are correct and reload work assignment metadata.

ESS-06583
Cannot delete bound work assignment {0}.

Category:
Other

Cause:
A work assignment that is bound may not be deleted.

Action:
Unbind the work assignment and then delete it.

ESS-06584
Reloading metadata for work assignment {0}.

Category:
Other

Cause:
Reloaded the work assignment metadata.

Action:
No action is necessary.

ESS-06585
Unable to bind work assignment {0} due to invalid workshift {1}.

Category:
Other

Cause:
In order to bind a work assignment, each of its workshifts must have an allocation of at least one. If the workshift has a schedule, the schedule must be unexpired, and the workshift duration must be > 0.

Action:
Fix the workshift and try again to bind the work assignment.

ESS-06586
Work assignment must include at least one workshift to be bound, {0}.

Category:
Other

Cause:
To be bound, a work assignment must have at least one workshift and be active.

Action:
Fix the work assignment and try again to bind it.

ESS-06587
Invalid update of a bound work assignment {0}.

Category:
Other

Cause:
A work assignment that is bound must have at least one workshift.

Action:
Add at least one workshift to the work assignment and retry the update.

ESS-06588
Failed to bind the ESS internal work assignment. {0}.

Category:
Other

Cause:
Unable to bind the ESS internal work assignment. The server will be started without the binding, and the default work assignment will be used.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06589
Binding the ESS internal work assignment.

Category:
Other

Cause:
The ESS internal work assignment is being bound for a new server.

Action:
No action is necessary.

ESS-06590
Error encountered by the worker for work assignment {0}.

Category:
Other

Cause:
Error encountered by worker for work assignment.

Action:
Review the log file for underlying causes.

ESS-06592
Error while processing request {0} for application {1}.

Category:
Other

Cause:
Error while processing request for application

Action:
Review the log file for underlying causes.

ESS-06593
Required property, {0}, is not present in message received for work assignment {1}.

Category:
Other

Cause:
Required property is not present in message received for work assignment.

Action:
Add the required request property for work assignment.

ESS-06594
Failed to schedule additional work for work assignment {0}. {1}

Category:
Other

Cause:
Failed to schedule additional work for work assignment.

Action:
Review the log file for underlying causes.

ESS-06595
Failed to update request history for request {0}.

Category:
Other

Cause:
Failed to update request history for request.

Action:
Review the log file for underlying causes.

ESS-06610
Failed processing request {0}, {1} stage.

Category:
Other

Cause:
Failed processing request.

Action:
Review the log file for underlying causes.

ESS-06617
Failed to extract event information for event name {0}.

Category:
Other

Cause:
Failed to extract event information for event name.

Action:
Review the log file for underlying causes.

ESS-06618
Error while dispatching event {0}, request {1}, to request listeners.

Category:
Other

Cause:
Error while dispatching event to request listeners.

Action:
Review the log file for underlying causes.

ESS-06620
Failed to get an endpoint for application {0}.

Category:
Other

Cause:
Failed to get an endpoint for application. Endpoint not available for processing.

Action:
Make sure endpoint application is available for processing.

ESS-06621
Error while calling endpoint for application {0}.

Category:
Other

Cause:
Failure encountered while calling endpoint for application.

Action:
Ensure application is deployed and running.

ESS-06622
Error while calling endpoint for application {0}, method {1}.

Category:
Other

Cause:
Error occured while calling endpoint for application.

Action:
Ensure application is deployed and running.

ESS-06630
Error starting work manager work.

Category:
Other

Cause:
An error occurred starting work mananger work.

Action:
None

ESS-06631
Cannot allocate thread. The maximum number of threads has been allocated for this pool: {0}

Category:
Other

Cause:
The maximum threads for a work pool has been reached.

Action:
None

ESS-06632
Cannot allocate thread. The client maximum number of threads has been allocated for this pool: {0}

Category:
Other

Cause:
The client maximum threads for a work pool has been reached.

Action:
None

ESS-06640
Error encountered by worker.

Category:
Other

Cause:
Error encountered by worker.

Action:
Review the log file for underlying causes.

ESS-06641
Failed to schedule additional work. {0}

Category:
Other

Cause:
Failed to schedule additional work.

Action:
Review the log file for underlying causes.

ESS-06645
Specialization is incorrectly formed and invalid for work assignment {0}. {1}

Category:
Other

Cause:
The work assignment specialization is incorrectly formed and invalid.

Action:
Fix the work assignment specialization and try again.

ESS-06646
Exclusive binding requires non-empty specialization, work assignment {0}.

Category:
Other

Cause:
Exclusive binding requires the work assignment specialization is non-empty.

Action:
Define a specialization for the work assignment and try binding it again.

ESS-06647
Exclusive mode is not allowed for {1} scoped binding, work assignment {0}.

Category:
Other

Cause:
Invalid binding mode for binding with the given scope.

Action:
Either bind the work assignment in standard mode or use a different scope (standard or group).

ESS-06700
Failed to check in event work {0} for {1} event, request {2}.

Category:
Other

Cause:
The event work for the given event could not be checked in or deleted.

Action:
The event work operation should be automatically retried, so no action is necessary.

ESS-06701
Failed to publish request listener event during processing of work {0}. Event: {1}, request: {2}.

Category:
Other

Cause:
An error occurred during an attempt to publish an event to be sent to the event listener of a request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06710
Unable to dispatch event {0} for request {1} to event listener.

Category:
Other

Cause:
The event work is not checked out to a specific instance.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06711
Error invoking event listener for request {0}. Event name: {1}, event request: {2}

Category:
Other

Cause:
Event listener was invoked and failed with an error.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06712
Event listener action for event {0}, request {1}. Status: [{2}], Message: [{3}]

Category:
Other

Cause:
Information from EventListenerAction returned by the listener.

Action:
None

ESS-06713
Delivery limit reached for event {0}, request {1}. No further delivery attempts will be made.

Category:
Other

Cause:
The event has been delivered to the event listener the maximum allowed times.

Action:
None

ESS-06714
Failed to authenticate user {0}. Dispatch event {1} for request {2} as an unprivileged call. Error: [{3}]

Category:
Other

Cause:
Failed to authenticate user. Event listener will be invoked in an unprivileged block.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06750
RequestId {0} with job definition {1} from hosting application {2}, is still in RUNNING state and holding up quiescing of ESS Server!

Category:
Other

Cause:
A job is still running in 2nd stage of ESS Quiesce and holding up ESS server from quiescing.

Action:
Update job logic to ensure it checks server quiesce and exits in time.

ESS-06751
Quiesce state update in Hosting App cache failed for hosting application {0}.

Category:
Other

Cause:
Quiesce state update in Hosting App cache failed for specified hosting app.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06752
ESS instance Quiesce state initialized to retrieved persisted quiesce state = {0}.

Category:
Other

Cause:
ESS instance Quiesce state initialized to retrieved persisted quiesce state.

Action:
No action is necessary.

ESS-06753
No persisted quiesce state found for this instance.

Category:
Other

Cause:
No persisted quiesce state found for this instance.

Action:
No action is necessary.

ESS-06754
Setting instance Quiesce state to {0}.

Category:
Other

Cause:
Setting Quiesce state to specified quiesce state.

Action:
No action is necessary.

ESS-06755
ESS instance is in an incompatible state and cannot transition to {0}.

Category:
Other

Cause:
ESS instance is in an incompatible state and cannot transition to specified quiesce state.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06756
QuiesceESS operation invoked with the following arguments:

Category:
Other

Cause:
QuiesceESS operation invoked with specified args.

Action:
No action is necessary.

ESS-06757
QuiesceESS operation invoked with invalid arguments, ignoring specified quiesce operation.

Category:
Other

Cause:
QuiesceESS operation invoked with invalid argumentss.

Action:
Check quiesceESS operations arguments and correct them.

ESS-06758
Forced UnQuiesce done, as Non-idempotent quiesce operation invoked, with instance in {0} state.

Category:
Other

Cause:
Forced UnQuiesce done, as Non-idempotent quiesce operation invoked, with an active quiesce state.

Action:
No action is necessary.

ESS-06759
Non-idempotent scheduled operation invoked resulting in Quiesce schedule override.

Category:
Other

Cause:
Non-idempotent scheduled operation invoked resulting in Quiesce schedule override.

Action:
No action is necessary.

ESS-06760
UnQuiesceESS operation transitioning instance from {0} state to POST_QUIESCE state.

Category:
Other

Cause:
UnQuiesce operation transitioning instance from specified Quiesce state to POST_QUIESCE state.

Action:
No action is necessary.

ESS-06761
Runtime service exception retrieving request details in Quiesce state.

Category:
Other

Cause:
Runtime service exception encountered retrieving request details in Quiesce state.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06762
Runtime service exception querying for running {0} jobs in Quiesce state.

Category:
Other

Cause:
Runtime service exception querying for running jobs in Quiesce state.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06763
Error retrieving persisted quiesce state or schedule for this instance.

Category:
Other

Cause:
Error retrieving persisted quiesce state or schedule for this instance.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06764
Error persisting quiesce state or schedule for this instance.

Category:
Other

Cause:
Error persisting quiesce state or schedule for this instance.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06765
Error terminating running job for request {0} in second stage of quiesce state.

Category:
Other

Cause:
Error terminating running job in second stage of quiesce state.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06800
Error handling {0} event for request {1} by request dispatcher.

Category:
Other

Cause:
Error handling event for request by request dispatcher.

Action:
Review the log for underlying causes.

ESS-06802
Request {0} is in {1} state. Skipping the processing.

Category:
Other

Cause:

Action:

ESS-06803
Request {0} is in {1} state. Skipping processing and deleting from wait queue.

Category:
Other

Cause:

Action:

ESS-06804
Request {0} has EXPIRED. Skipping processing and deleting from wait queue.

Category:
Other

Cause:

Action:

ESS-06805
Request {0} is in illegal state {1} ({2}). Skipping processing and deleting from wait queue.

Category:
Other

Cause:
Request is in illegal state. Skipping processing and deleting from wait queue.

Action:
Review the log for underlying causes.

ESS-06806
Request {0} not found in runtime store. Skipping processing and deleting from wait queue.

Category:
Other

Cause:
Request not found in runtime store. Skipping processing and deleting from wait queue.

Action:
No Action is necessary.

ESS-06807
Error occurred while dispatching requests.

Category:
Other

Cause:
An error occurred while attempting to dispatch one or more requests.

Action:
Review the log file to determine the nature of the problem.

ESS-06816
Error processing request {0} by request dispatcher.

Category:
Other

Cause:
An error occurred during the request dispatching process for the given request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06817
No subrequests exist for paused request {0}. Request execution will be resumed.

Category:
Other

Cause:
No sub-requests are active for this paused request.

Action:
None

ESS-06820
Failed to retrieve Schedule for request {1}.

Category:
Other

Cause:
Failed to retrieve Schedule needed to determine the next schedule execution time.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06821
Failed to update error information for request {0}. {1}

Category:
Other

Cause:
Failed to update the error information for a request.

Action:
Review the log file for to determine the nature of the problem.

ESS-06830
Error occurred processing post-execution work for request {0}. WorkId: {1}

Category:
Other

Cause:
An error occurred while processing a post-execution work unit.

Action:
Review the log file to determine the nature of the problem.

ESS-06831
Cannot process post-execution work for request {0}. State is {1}, process phase is {2}. WorkId: {3}

Category:
Other

Cause:
The request state and/or process phase prevents a post-execution work unit for a request from being processed. The work will be discarded.

Action:
None

ESS-06832
Failed to publish the metadata change event for {0}, appName={1}. {2}

Category:
Other

Cause:
Failed to publish the change event for the metadata change notification.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06833
Unrecognized metadata change type {0}, appName={1}, metaId={2}, origServer={3}

Category:
Other

Cause:
Unrecognized metadata change type in metadata change event.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06834
Ignoring change event as metadata cannot be found: {0}, appName={1}. {2}

Category:
Other

Cause:
Received metadata change event and metadata does not exist; it may have been deleted since the change happened.

Action:
Review the log file for attached exceptions to determine the nature of the problem, if any.

ESS-06835
Performing automatic refresh of metadata for request {0}, metadata {1}.

Category:
Other

Cause:
Metadata used by the request has changed and is being automatically refreshed.

Action:
No action is required.

ESS-06836
Changes to metadata prevent automatic refresh for request {0}, metadata {1}.

Category:
Other

Cause:
Metadata used by the request has changed but cannot be refreshed because the changes are not allowed for automatic refresh.

Action:
No action is required. For automatic refresh, only customizable parameters may have been changed.

ESS-06837
Unable to refresh job metadata at this time for request {0}.

Category:
Other

Cause:
Temporarily unable to refresh changed metadata for the request.

Action:
No action is required. The request may be refreshed in the future.

ESS-06838
Unable to access metadata in runtime store for request {0}, metadata {1}.

Category:
Other

Cause:
Unable to access cached metadata for the request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06839
Metadata already exists in runtime store for request {0}, metadata {1}.

Category:
Other

Cause:
The metadata already exists in the cache in the runtime store for the request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06840
Failed to insert metadata change notification for application {0}, change type {1}, metadata id {2}.

Category:
Other

Cause:
Failed to add the metadata change notification to the runtime store.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06841
Failed to insert metadata change notification for application {0}, change type {1}, metadata id {2}.

Category:
Other

Cause:
Failed to add the metadata change notification to the runtime store.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06842
Unable to access metadata change notifications.

Category:
Other

Cause:
Unable to access metadata change notifications.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-06843
Unable to determine the logical application name for deployed application "{0}".

Category:
Other

Cause:
Unable to determine the logical application that should be used for a metadata change notification.

Action:
Review the log file for information to determine the nature of the problem, and ensure the logical application name is defined.

ESS-06844
Failed to remove parameter {0} for request {1}.

Category:
Other

Cause:
Unable to remove the parameter for the request during a metadata refresh.

Action:
Review the log file for information to determine the nature of the problem.

ESS-06845
Failed to remove the read-only constraint for parameter {0}, request {1}.

Category:
Other

Cause:
Unable to remove the read-only constraint for the request parameter during a metadata refresh.

Action:
Review the log file for information to determine the nature of the problem.

ESS-06846
Parameter "{0}" is now read only for request {1}. Previous update is discarded.

Category:
Other

Cause:
Due to a metadata refresh, the parameter is now read-only. The parameter had been updated previously, and that update has been discarded.

Action:
No action is required.

ESS-06847
Failed to remove runtime metadata for request {0}.

Category:
Other

Cause:
Unable to remove cached runtime metadata for the request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-07000
Error handling {0} event for request {1} by request processor.

Category:
Other

Cause:
Error handling event for request by request processor.

Action:
Review the log file for underlying causes.

ESS-07001
Error processing request {0}.

Category:
Other

Cause:
Error processing request.

Action:
Review the log file for underlying causes.

ESS-07002
Failed to obtain system executable wrapper for request {0}.

Category:
Installation

Cause:
Possible causes include unknown job type, user login error, classloading issues...

Action:
Review the causeBy exception clause to determine the specific failure.

ESS-07003
Execution warning for request {0}. Reason: {1}

Category:
Other

Cause:
Execution error warning for request.

Action:
Review the log file for underlying causes.

ESS-07004
Execution error for request {0}. Reason: {1}

Category:
Other

Cause:
Execution error for request.

Action:
Review the log file for underlying causes.

ESS-07005
Execution cancelled for request {0}. Reason: {1}

Category:
Other

Cause:
The job execution has been cancelled.

Action:
Check the cause for the exception. If the cause is not given, you can adjust logging level to fine and retry it.

ESS-07006
Failed to cancel request {0}.

Category:
Other

Cause:
Failed to cancel request.

Action:
Review the log file for underlying causes.

ESS-07012
Invalid action ({0}) returned from pre-process callout for request {1}. Setting to {2} state.

Category:
Other

Cause:
Invalid action returned from pre-process callout for the request.

Action:
Review the log for underlying causes.

ESS-07013
Invalid action ({0}) returned from post-process callout for request {1}. Setting to {2} state.

Category:
Other

Cause:
Invalid action returned from pre-process callout for the request.

Action:
Review the log for underlying causes.

ESS-07014
Delaying processing of request {0} by {1} minutes.

Category:
Other

Cause:
The pre-process callback return value indicated that request processing should be delayed.

Action:
No action required. The request will be retried after the delay.

ESS-07015
Error occurred during cleanup of database job for request {0}.

Category:
Other

Cause:
An error occurred while performing post-execution clean tasks for an Oracle Scheduler job used to execute a SQL job request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-07016
Failed processing update event for request {0}.

Category:
Other

Cause:
An error occurred processing an update event.

Action:
Contact Oracle Support Services

ESS-07017
Cannot process update event for request {0} in state {1}.

Category:
Other

Cause:
The request is in an illegal state for an update event.

Action:
None

ESS-07018
Cannot process update event for request {0} in state {1}.

Category:
Other

Cause:
The request is in an illegal state for an update event.

Action:
None

ESS-07019
Error processing request {0}. {1}

Category:
Other

Cause:
Error processing request.

Action:
Review the log file for underlying causes.

ESS-07020
Failed get an endpoint for application {0}.

Category:
Other

Cause:
Failed get an endpoint for application.

Action:
No action is necessary.

ESS-07021
Invalid work unit action for request {0}, work unit {1}, action {2}.

Category:
Other

Cause:
Invalid work unit action for request.

Action:
Report the failure to Oracle support as it could be a bug in ESS.

ESS-07022
Invalid endpoint action for request {0}, stage {1}, action {2}.

Category:
Other

Cause:
Invalid endpoint action for request.

Action:
Report the failure to oracle support.

ESS-07023
Error processing timed out requests. {0}.

Category:
Other

Cause:
An error occurred attempting to process a timed out request.

Action:
None

ESS-07024
Rejecting update event for request {0}. {1}. Result status = {2}. Result message = {3}. Message body = {4}.

Category:
Other

Cause:
The request is in an illegal state for an update event.

Action:
None

ESS-07025
Failed to allocate an asynchronous worker for request {0}. ({1}, {2}). ExecutionType = {3}.

Category:
Other

Cause:
Failed to allocate an asynchronous worker.

Action:
None

ESS-07026
Failed to release an asynchronous worker for request {0}. ({1}, {2}). ExecutionType = {3}.

Category:
Other

Cause:
Failed to release an asynchronous worker.

Action:
None

ESS-07027
Failed to terminate request {0}.

Category:
Other

Cause:
Failed to terminate request.

Action:
Review the log file for underlying causes.n

ESS-07028
Error invoking or executing application endpoint for request {0}. Check application status of logical application {1}.

Category:
Other

Cause:
An error occurred invoking a method on the endpoint of this application.

Action:
Check that the application is deployed and running successfully.

ESS-07029
Asynchronous throttle configuration does not exist for Workshift = {0}.

Category:
Other

Cause:
The async throttle configuration does not exist for the workshift.

Action:
Contact Oracle Support Services

ESS-07030
Recovering update work unit {0} for request {1} that may have been executing. There is a possibility of redelivery.

Category:
Other

Cause:
An update event is being recovered from a stage where redelivery is possible.

Action:
None

ESS-07031
Error in transaction processing for request {0}. The transaction is eligible to be retried

Category:
Other

Cause:
A recoverable SQL error was encountered

Action:
None

ESS-07032
Work unit execution attempt, {0}, does not match request execution attempt, {1}, for request {2}.

Category:
Other

Cause:
The current work unit is for an older request execution attempt

Action:
None

ESS-07033
Job logic indicated a system error occurred while executing an asynchronous java job for request {0}. Job error is: {1}.

Category:
Other

Cause:
The job indicated that an error occurred

Action:
Examine the innermost exception, if present, for the cause

ESS-07034
Job logic indicated a business error occurred while executing an asynchronous java job for request {0}. Job error is: {1}.

Category:
Other

Cause:
The job indicated that a business error occurred

Action:
Examine the innermost exception, if present, for the cause

ESS-07035
Job logic indicated a warning occurred while executing an asynchronous java job for request {0}. Job warning is: {1}.

Category:
Other

Cause:
The job indicated that a warning occurred

Action:
Examine the innermost exception, if present, for the cause

ESS-07036
There was a system error while processing request {0} from which it cannot be recovered. Please check the server logs. (Process phase = {1}).

Category:
Other

Cause:
The request needed to be recovered because of a system error, but cannot be recovered safely

Action:
None

ESS-07037
Error performing substitutions for request {0}

Category:
Other

Cause:
An error occurred while performing substitution in a request parameter or other user input. This may be for process type job command line or environment variable.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-07038
Failed to initialize job context extensions for request {0} at stage {1}

Category:
Other

Cause:
An error occurred while initializing job context extensions.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-07039
Failed to cleanup job context for request {0} at stage {1}

Category:
Other

Cause:
An error occurred while cleaning job context extensions.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-07040
Failed to terminate job context for request {0}

Category:
Other

Cause:
An error occurred while terminating job context extensions.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-07041
Failed to retrieve alternate environment for application {0}

Category:
Other

Cause:
An error occurred while retrieving alternate application environment properties.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-07042
Expected class {0} not available for request mode {1}

Category:
Other

Cause:
An error instantiating an extensions class.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-07043
Failed to get platform request file directory for request {0}

Category:
Other

Cause:
An error occurred discovering the platform request file directory.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-07044
Failed to instantiate EJB job request {0}

Category:
Other

Cause:
Failed to instantiate RemoteExecutable object for a EJB request.

Action:
Make sure the bean implements RemoteExecutable and the parameters JNDI_MAPPED_NAME, JNDI_PROVIDER_URL are specified in job definition.

ESS-07045
Failed to execute EJB job request {0}. Reason: {1}

Category:
Other

Cause:
Failed to execute RemoteExecutable object for a EJB request.

Action:
Review the log file for attached exceptions to determine the nature of the problem.

ESS-07046
Failed to cancel EJB job request {0}

Category:
Other

Cause:
Failed to cancel RemoteCancellableExecutable object for a EJB request.

Action:
Review the log file for attached exceptions to determine the nature of the problem. Make sure the EJB implement RemoteCancellableExecutable interface.

ESS-07047
Metadata parameter {0} not specified in job definition for request {1}.

Category:
Other

Cause:
Validation failed for EJB request. One or more mandatory parameters of EJB job not set.

Action:
Make sure the mandatory parameters are specified in job definition.

ESS-07048
Error while retrieving credentials for CSF Key {0} while processing request {1}.

Category:
Other

Cause:
Error while retrieving CSF credentials. The configuration is either null or invalid.

Action:
Make sure the CSF configuration is proper.

ESS-07049
Error while retrieving Ess Configuration for application {0} while processing request {1}.

Category:
Other

Cause:
Error while retrieving values of EssConfiguration . The configuration is either null or invalid.

Action:
Make sure the configuration is proper.

ESS-07050
Refreshing runtime incompatibilities for request {0}.

Category:
Other

Cause:
Refreshing runtime incompatibilities for the request.

Action:
No action is required.

ESS-07060
Invalid work unit action {0} for work unit {1}.

Category:
Other

Cause:
Invalid work unit action.

Action:
Report the failure to Oracle support as it could be a bug in ESS.

ESS-07061
An error occurred initiating processing of an update work unit for request {0}.The incoming asynchronous status is {1}.Error message: [{2}] {3}

Category:
Other

Cause:
The asynchronous java job callback to update the status could not be processed.

Action:
Examine error message

ESS-07200
Invalid workDirectory specified for spawned job request {0}: {1} does not exist.

Category:
Other

Cause:
Invalid workDirectory specified for spawned job request {0}: {1} does not exist.

Action:
Ensure requestFileDirectory configured and a valid workDirectory specified for request.

ESS-07201
Error launching spawnAgent for spawned job request {0}.

Category:
Other

Cause:
Error launching spawnAgent for spawned job request {0}.

Action:
Review log file for nested IOexception and resolve the issue.

ESS-07202
Error opening Output stream to spawnAgent for spawned job request {0}.

Category:
Other

Cause:
Error opening Output stream to spawnAgent for spawned job request {0}.

Action:
Review log file for nested IOexception and resolve the issue.

ESS-07203
spawnAgent terminated at launch for spawned job request {0}.

Category:
Other

Cause:
spawnAgent terminated at launch for spawned job request {0}.

Action:
Enable Agent log to find cause and resolve.

ESS-07204
spawnAgent cannot spawn process for spawned job request {0} with command line: {1}. Cause={2}

Category:
Other

Cause:
spawnAgent cannot spawn process for spawned job request {0} with cmdline: {1}. Cause={2}.

Action:
Check error cause and update spawned job definition.

ESS-07205
spawnAgent terminated before completion of spawned process for spawned job request {0} with command line: {1}.

Category:
Other

Cause:
spawnAgent terminated before completion of spawned process for spawned job request {0} with cmdline {1}.

Action:
Enable Agent log to find cause and resolve.

ESS-07206
Error waiting for completion of spawned job request {0} with command line: {1}.

Category:
Other

Cause:
Error waiting for completion of spawned job request {0} with cmdline: {1}.

Action:
Review log file for nested IOexception and resolve the issue.

ESS-07207
Invalid Exit Code returned by spawned process for spawned job request {0} with command line: {1}.

Category:
Other

Cause:
Invalid Exit Code returned by spawned process for spawned job request {0} with cmdline: {1}.

Action:
Enable Agent log to find cause and resolve.

ESS-07208
Error during post-completion cleanup for spawned job request {0} with command line: {1}.

Category:
Other

Cause:
Error during post-completion cleanup for spawned job request {0} with cmdline: {1}.

Action:
Review log file for nested exception and resolve.

ESS-07209
Error retrieving DomainConfigDirectory using JRF ServerPlatformSupportFactory API.

Category:
Other

Cause:
Error retrieving DomainConfigDirectory using JRF ServerPlatformSupportFactory API.

Action:
Review log file for nested exception and resolve.

ESS-07210
Error registering shutdown hook for spawned job request {0}.

Category:
Other

Cause:
Error registering shutdown hook for spawned job request {0}.

Action:
Review log file for nested exception and resolve.

ESS-07211
Error deregistering shutdown hook for spawned job request {0}.

Category:
Other

Cause:
Error deregistering shutdown hook for spawned job request {0}.

Action:
Review log file for nested exception and resolve.

ESS-07212
Error updating processId for spawned job request {0}.

Category:
Other

Cause:
Error updating processId for spawned job request {0}.

Action:
Review log file for nested exception and resolve.

ESS-07213
Using Perl SpawnAgent {1} with perl interpreter at {2} for spawned job request {0}.

Category:
Other

Cause:
Using Perl SpawnAgent {1} with perl interpreter at {2} for spawned job request {0}.

Action:
None

ESS-07214
Error locating Perl spawnAgent script for spawned job request {0}.

Category:
Other

Cause:
Error locating Perl SpawnAgent script for spawned job request {0}.

Action:
Contact Administrator.

ESS-07215
Error locating Perl interpreter for spawned job request {0}.

Category:
Other

Cause:
Error locating Perl interpreter for spawned job request {0}.

Action:
Contact Administrator.

ESS-07216
Using Java SpawnAgent from {1} for spawned job request {0}.

Category:
Other

Cause:
Using Java SpawnAgent from {1} for spawned job request {0}.

Action:
None

ESS-07217
Error retrieving SpawnAgent configuration.

Category:
Other

Cause:
Error retrieving SpawnAgent configuration.

Action:
Review log file for nested exception. Contact Administrator.

ESS-07218
Unable to locate Perl interpreter from FusionApps WebTier location.

Category:
Other

Cause:
Unable to locate Perl interpreter from FusionApps WebTier location.

Action:
None

ESS-07300
Invalid WebServiceJobDefinition for request {0}, {1} property value is invalid.

Category:
Other

Cause:
Invalid WebServiceJob Definition: identified property value is invalid.

Action:
Specify a valid value for the identified property in WebServiceJobDefinition.

ESS-07301
Post-substitution WebService INVOKE_MESSAGE for request {0}: {1}

Category:
Other

Cause:
PostSubstitution WebService Invoke Message.

Action:
None

ESS-07302
WebService INVOKE_MESSAGE Substitution Error for request {0}.

Category:
Other

Cause:
Substitution error while processing WebService INVOKE_MESSAGE.

Action:
Specify a valid xml for INVOKE_MESSAGE property in WebServiceJobDefinition.

ESS-07303
WebService WSDL URL Substitution Error for request {0}.

Category:
Other

Cause:
Substitution error while processing WebService Wsdl URL.

Action:
Review WS_WSDL_URL property value in WebServiceJobDefinition.

ESS-07304
WebService WSDL URL Retrieval Error for request {0}.

Category:
Other

Cause:
Error retrieving WebService Wsdl from substituted URL.

Action:
Review WS_WSDL_URL property value in WebServiceJobDefinition.

ESS-07305
Invalid WebService Endpoint URL for request {0} in wsdl retrieved from {1}.

Category:
Other

Cause:
Invalid WebService Endpoint URL in retrieved wsdl.

Action:
Review WS_WSDL_URL property value in JobDefinition and Endpoint URL value in specified wsdl.

ESS-07306
WS_SECURITY_OPTION property not specified OR Invalid WS_SECURITY_OPTION property value in WebServiceJob JobDefinition for request {0}.

Category:
Other

Cause:
WS_SECURITY_OPTION property not specified OR Invalid WS_SECURITY_OPTION property value in WebServiceJobDefinition.

Action:
Review WS_SECURITY_OPTION property value in JobDefinition, if specified.

ESS-07307
WS_HTTP_BASIC_AUTH_CSF_KEY not configured in JobDefinition for request {0}.

Category:
Other

Cause:
WS_HTTP_BASIC_AUTH_CSF_KEY not configured in WebServiceJob Definition.

Action:
Specify a valid CSF key for WS_HTTP_BASIC_AUTH_CSF_KEY property in WebServiceJobDefinition.

ESS-07308
Error using JRF PortConfig API to determine ESS WebService URL Prefix.

Category:
Other

Cause:
Error using JRF PortConfig API to determine ESS WebService URL Prefix.

Action:
JRF Portability issue. Contact Administrator.

ESS-07309
Computed WebService Callback URL for Async WebServiceJob: {0}.

Category:
Other

Cause:
Computed WebService Callback URL.

Action:
None

ESS-07310
Error invoking webservice operation {1} for request {0}.

Category:
Other

Cause:
Error invoking webservice operation.

Action:
Review log file for attached exception and update JobDefinition.

ESS-07311
WebService operation {1} for request {0} results in SOAPFault with FaultCode={2} and FaultString={3}.

Category:
Other

Cause:
Invoking webservice operation results in a SOAPFault.

Action:
Review SOAPFault and update WebService JobDefinition properties.

ESS-07312
Error saving WebService operation messageId for request {0}.

Category:
Other

Cause:
Error saving WebService operation messageId.

Action:
Review log file for attached exception.

ESS-07313
Error retrieving WebService operation messageId for request {0}.

Category:
Other

Cause:
Error retrieving WebService operation messageId.

Action:
Review log file for attached exception.

ESS-07314
WebService operation for request {0} cannot be cancelled as Cancel Operation properties not specified in WebServiceJobDefinition.

Category:
Other

Cause:
WebService operation for request cannot be cancelled as Cancel operation properties not specified in WebServiceJobDefinition.

Action:
Review Cancel operation properties in WebServiceJobDefinition.

ESS-07315
WebService operation for request {0} cannot be cancelled, as Cancel message specified in WebServiceJobDefinition is invalid.

Category:
Other

Cause:
WebService operation for request cannot be cancelled as Cancel message specified in WebServiceJobDefinition is invalid.

Action:
Review Cancel operation properties in WebServiceJobDefinition.

ESS-07316
WebService WS_CANCEL_MESSAGE Substitution Error for request {0}.

Category:
Other

Cause:
Substitution error while processing WebService Cancel message.

Action:
Review WS_CANCEL_MESSAGE property in WebServiceJobDefinition.

ESS-07317
Error invoking webservice Cancel operation {1} for request {0}.

Category:
Other

Cause:
Error Cancelling webservice operation.

Action:
Review log file for attached exception and update Cancel operation properties in JobDefinition.

ESS-07318
WebService Cancel operation {1} for request {0} results in SOAPFault with FaultCode={2} and FaultString={3}.

Category:
Other

Cause:
Invoking webservice Cancel operation results in a SOAPFault.

Action:
Review SOAPFault and update WebService JobDefinition properties.

ESS-07319
Error retrieving webservice SOAPResponse payload for request {0}.

Category:
Other

Cause:
Error retrieving webservice SOAPResponse payload.

Action:
Review log file for attached exception and and update WebService JobDefinition properties.

ESS-07320
Error capturing webservice response as Job Output for request {0}.

Category:
Other

Cause:
Error capturing webservice response as Job Output.

Action:
Review log file for attached exception.

ESS-07321
WebService Job Output for request {0}: {1}.

Category:
Other

Cause:
WebServiceJob Output.

Action:
None

ESS-07322
Error retrieving credentials from CredentialStore using CSF key {0}.

Category:
Other

Cause:
Error retrieving CSF Credentials from CredentialStore.

Action:
Review CSF key in WebServiceJobDefinition.

ESS-07323
No base URL is specified for relative URL {0} = {1} for request {2}.

Category:
Other

Cause:
A required base URL was not specified for the given relative URL

Action:
Specify the corresponding base URL as an ESS system property or in the application configuration.

ESS-07324
Error retrieving WebService JobDefinition for request {0}.

Category:
Other

Cause:
Error retrieving WebService JobDefinition for request {0}.

Action:
Review log file for attached exception.

ESS-07325
Error retrieving wsa:relatesTo addresssing header from callback message using DISI ServiceRequestTransport.

Category:
Other

Cause:
Error retrieving wsa:relatesTo addresssing header from callback message using DISI ServiceRequestTransport.

Action:
Review log file for attached exception.

ESS-07326
Invalid SOAP response message, error processing message by WebServiceJob Callback servlet.

Category:
Other

Cause:
Invalid SOAP response message, error processing message by WebServiceJob Callback servlet.

Action:
Review log file for attached exception. Verify async callback message is a valid SOAP response

ESS-07327
Error processing WebServiceJob callback response in ServiceResponseTransport.

Category:
Other

Cause:
Error processing WebServiceJob callback response in ServiceResponseTransport.

Action:
Review log file for attached exception.

ESS-07328
Error processing WebServiceJob callback message in ProviderRequest.

Category:
Other

Cause:
Error processing WebServiceJob callback message in ProviderRequest.

Action:
Review log file for attached exception.

ESS-07329
WebServiceJob Progress message not permitted for request {0}.

Category:
Other

Cause:
WebServiceJob Progress message not permitted for request {0}.

Action:
Review WebServiceJob progress message usage recommendations.

ESS-07332
Error registering Policy Assembly {0} with OWSM.

Category:
Other

Cause:
Error registering Policy Assembly {0} with OWSM.

Action:
Review PolicyAssembly ResourcePattern.

ESS-07360
EssPolicyManager instance lookup attempted passing a NULL PolicyContext.

Category:
Other

Cause:
EssPolicyManager instance lookup attempted passing a NULL PolicyContext

Action:
Review log file for details. Contact administrator.

ESS-07361
EssPolicyManager instance lookup attempted passing empty or NULL application name.

Category:
Other

Cause:
EssPolicyManager instance lookup attempted passing empty or NULL application name

Action:
Review log file for details. Contact administrator.

ESS-07362
Error publishing WsmPolicyUpdateEvent for application {0}.

Category:
Other

Cause:
Error publishing WsmPolicyUpdateEvent for application {0}.

Action:
Review log file and contact Administrator.

ESS-07364
Error deregistering Policy Assembly {0} with OWSM.

Category:
Other

Cause:
Error deregistering Policy Assembly {0} with OWSM.

Action:
Review PolicyAssembly ResourcePattern.

ESS-07365
Error creating Policy Assembly for request {0}.

Category:
Other

Cause:
Error creating Policy Assembly for request {0}.

Action:
Review log file for attached exception.

ESS-07366
Error retrieving Policy Assembly for job definition {0}.

Category:
Other

Cause:
Error retrieving Policy Assembly for job definition {0}.

Action:
Review log file for attached exception.

ESS-07367
Error validating {0} Policy Subject registration with OWSM Policy Access Point for request {1}.

Category:
Other

Cause:
Error validating {0} Policy Subject registration with OWSM Policy Access Point for request {1}.

Action:
Review log file for owsm . Contact Administrator.

ESS-07500
Error parsing attribute {0}. {1}

Category:
Other

Cause:
An error is present in a command attribute format.

Action:
Contact Oracle Support Services.

ESS-07501
Error starting command worker.

Category:
Other

Cause:
An error occurred starting a command worker.

Action:
None

ESS-07502
Failed to set request state to VALIDATION_FAILED for request {0}. {1}

Category:
Other

Cause:
An error occurred while setting the state of the request to VALIDATION_FAILED.

Action:
None

ESS-07503
Document conversion failed for command work {0}. Command type: {1}, request: {2}.

Category:
Other

Cause:
Failed converting DOC Document for command work.

Action:
None

ESS-07505
Validation of request {0} failed.

Category:
Other

Cause:
Validation of the request has failed.

Action:
Check logs and error information for details.

ESS-07506
Failed to check in command work {0} for {1} command, request {2}.

Category:
Other

Cause:
The work for the given command could not be checked in or deleted.

Action:
The command work operation should be automatically retried, so no action is necessary.

ESS-07507
Unknown command type, {0}, for command work {1}.

Category:
Other

Cause:
The command work has an unknown commad type.

Action:
None

ESS-07508
Error calling endpoint for application {0} during processing of {1} command for request {2}.

Category:
Other

Cause:
The command work has an unknown commad type.

Action:
None

ESS-07509
Failed to execute command {0} for request {1} for command work {2}.

Category:
Other

Cause:
An error occurred executing the command.

Action:
Review the log file for the cause.

ESS-07510
Failed to update command {0} for request {1} for command work {2}.

Category:
Other

Cause:
An error occurred updating the command.

Action:
Review the log file for the cause.

ESS-07540
Failed to complete request {0} during group cleanup for execution group {1}, isolation group {2}.

Category:
Other

Cause:
Clean up of request failed during execution group removal.

Action:
None. The action will be automatically retried.

ESS-07541
Failed to get list of incomplete requests for execution group {0}, isolation group {1}.

Category:
Other

Cause:
Retrieving requests during execution group removal failed.

Action:
None. The action will be automatically retried.

ESS-07542
Failed to remove registrations for execution group {0}, isolation group{1}.

Category:
Other

Cause:
Removing instance or application registrations failed during execution group removal.

Action:
None. The action will be automatically retried.

ESS-07543
Failed to lock recovery delete table.

Category:
Other

Cause:
Failed to lock the recovery delete table.

Action:
None. The action will be automatically retried.

ESS-07544
Failed to insert row for process group {0}, isolation group {1}, action {2}.

Category:
Other

Cause:
Failed to insert the entry into recovery delete table.

Action:
None. The action will be automatically retried.

ESS-07545
Failed to delete row for process group {0}, isolation group {1}, action {2}.

Category:
Other

Cause:
Failed to delete the entry from recovery delete table.

Action:
None. The action will be automatically retried.

ESS-07546
Failed to query row for process group {0}, isolation group {1}, action {2}.

Category:
Other

Cause:
Failed to query for the entry from recovery delete table.

Action:
None. The action will be automatically retried.

ESS-07552
Failed to insert configuration for application {0} in process group {1}.

Category:
Other

Cause:
Failed to insert the entry from essconfig table.

Action:
None.

ESS-07553
Failed to delete configuration for application {0} in process group {1}.

Category:
Other

Cause:
Failed to delete the entry from essconfig table.

Action:
None.

ESS-07554
Failed to update configuration for application {0} in process group {1}.

Category:
Other

Cause:
Failed to update the configuration for the given application.

Action:
None.

ESS-07555
Failed to query configuration for application {0} in process group {1}.

Category:
Other

Cause:
Failed to query the entry from essconfig table.

Action:
None.

ESS-07556
Failed to find configuration for application {0} in process group {1}.

Category:
Other

Cause:
The configuration for the given application could not be found

Action:
Check if the ESS logical application name is correct and that it is deployed to the current cluster.

ESS-07557
Configuration exists for application {0} in process group {1}.

Category:
Other

Cause:
Configuration is already present for the given application.

Action:
None.

ESS-07558
Failed to convert {2} for application {0} in process group {1}.

Category:
Other

Cause:
Conversion for an EssConfig or Customization object failed

Action:
None.

ESS-07559
Property {0} is immutable defined in the base application.

Category:
Other

Cause:
The given application configuration property is immutable and cannot be customized.

Action:
None.

ESS-07560
Property {0} is immutable.

Category:
Other

Cause:
The given application configuration property is immutable and cannot be customized.

Action:
None.

ESS-07561
Property name {0} is a reserved ESS property name.

Category:
Other

Cause:
The given application configuration property name is a reserved name.

Action:
None.

ESS-07562
Property {0} has been defined. An update operation should be used.

Category:
Other

Cause:
The given application configuration property has been defined.

Action:
Use update operation to customize the property.

ESS-07563
Failed to insert configuration for server {0} in process group {1}.

Category:
Other

Cause:
Failed to insert the entry into the server configuration table.

Action:
None.

ESS-07564
Failed to delete configurations in process group {0}.

Category:
Other

Cause:
Failed to delete the entry from server configuration table.

Action:
None.

ESS-07565
Failed to update configuration for server {0} in process group {1}.

Category:
Other

Cause:
Failed to update the configuration for the given server.

Action:
None.

ESS-07566
Failed to query configuration for server {0} in process group {1}.

Category:
Other

Cause:
Failed to query the entry from ess server config table.

Action:
None.

ESS-07567
Failed to find configuration for server {0} in process group {1}.

Category:
Other

Cause:
The configuration for the given server could not be found.

Action:
None.

ESS-07568
Configuration already exists for server {0} in process group {1}.

Category:
Other

Cause:
Configuration is already present for the given server name.

Action:
None.

ESS-07569
An error occurred while updating the Scheduler server configuration for server {0} in process group {1}.

Category:
Other

Cause:
An error occurred updating the ESS server configuration.

Action:
None.

ESS-07575
Error inserting wiring {0} with value {1} for group {2}.

Category:
Other

Cause:
Failed to store cross component wiring information.

Action:
None.

ESS-07576
Error retrieving wiring {0} from group {1}.

Category:
Other

Cause:
An error occurred retrieving cross component wiring information from the runtime store.

Action:
None.

ESS-07577
Error deleting all entries in wirings table.

Category:
Other

Cause:
An error occurred deleting cross component wiring information from the runtime store.

Action:
None.

ESS-07578
Failed to register listener for CCW configuration.

Category:
Other

Cause:
The cross component wiring configuration listener could not be registered.

Action:
Review the log file for the cause.

ESS-07579
Failed to unregister listener for CCW configuration.

Category:
Other

Cause:
The cross component wiring configuration listener could not be registered.

Action:
Review the log file for the cause.

ESS-07580
Cross component wiring configuration listener failed to process document change event.

Category:
Other

Cause:
An error occurred processing the notification from the ESS CCW configuration.

Action:
Review the log file for the cause.

ESS-07581
Failed to delete wirings for URNs {0} from group {1}.

Category:
Other

Cause:
An error occurred deleting cross component wiring information from the runtime store.

Action:
None.

ESS-07582
A logical cluster name must be specified for cross-component wiring enabled jobs. Parameter {0} for request {1} has substitution prefix WIRING.

Category:
Other

Cause:
The WIRING substitution prefix was used for a job without a logical cluster name.

Action:
Either specify a logical cluster name for the job or explicitly specify the property value.

ESS-07614
null

Category:
Programmatic

Cause:
Ranks are applicable only for requests of state WAIT and READY.

Action:
Specify a request in WAIT or READY state.

ESS-07701
{0} property must be positive and not null for request {1}.

Category:
Other

Cause:
Processed count or failed count property is negetive or null.

Action:
Provide valid values for Processed count or failed count property.

ESS-07702
{0} property must not be null or empty for request {1}.

Category:
Other

Cause:
Job Monitoring property is empty or null.

Action:
Provide valid values for Job monitoring property.

ESS-07703
Number of counters are limited to 5 per job for request {0}

Category:
Other

Cause:
Number of counters are limited to 5 per job.

Action:
Provide valid Counter number between 1 to 5.

ESS-07704
Counters have not been initialized for counter number {0} for request {1}.

Category:
Other

Cause:
Job Monitoring counter property are not initialized.

Action:
Job Monitoring counter property should be initialized before updating them.

ESS-07705
Counter name property can be initialized only once and have already been initialized with different value for counter number {0} for request {1}.

Category:
Other

Cause:
Counter Name property is already initialized with a different value.

Action:
Provide a valid counter name property.

ESS-07706
Total count property is not valid for counter number {0} for request {1}.

Category:
Other

Cause:
Total count property is not valid.

Action:
Provide a valid value for Total count.

ESS-07707
RuntimeService is null.

Category:
Other

Cause:
The ESS runtime service is null.

Action:
Provide a valid ESS runtime service.

ESS-07708
An unknown or unsupported state is specified: {0}.

Category:
Other

Cause:
An unknown or unsupported state is specified.

Action:
Provide a valid supported state.

ESS-07709
Job Monitoring counters cannot be initialized or updated as request {0} is already in {1} state.

Category:
Other

Cause:
Job Monitoring counter property cannot be initialized or updated as request has been cancelled.

Action:
Job Monitoring status updates not permitted when job has been cancelled.

ESS-07710
Total count property can not be updated. It has already been initialized for counter number {0} for request {1}.

Category:
Other

Cause:
Total count property is already initialized.

Action:
Total count property can't be updated once initialized.

ESS-07711
Job Monitoring message string is either with invalid format or counter information for request {0}. String Format: apiName=xxxx,counterNumber=xxxx,counterName=xxxx,totalCount=xxxx,processedCount=xxxx,failedCount=xxxx,counterKey=xxxx,enableJobCancelDetection=xxxx, where xxxx represents counter information.

Category:
Other

Cause:
Job monitor message string is either with invalid format or counter information. Format: apiName=xxxx,counterNumber=xxxx,counterName=xxxx,totalCount=xxxx,processedCount=xxxx,failedCount=xxxx, where xxxx represents counter information.

Action:
Correct the invalid job monitor message string.

ESS-07712
Job monitoring counter property {0} is not supported for this operation.

Category:
Other

Cause:
Job Monitoring Counter property is not supported for this operation.

Action:
Provide valid Job Monitoring counter property..

ESS-07713
A resource bundle is already registered and cannot be updated or reset for the request {0}.

Category:
Other

Cause:
A resource bundle is already registered for the request and cannot be updated or reset.

Action:
Resource bundle MUST be the same which is registered with this request.

ESS-08000
The value of filter is null.

Category:
Other

Cause:
The value of filter is null

Action:
Provide the correct privilege name.

ESS-08001
Invalid sec filter comparator.

Category:
Other

Cause:
Invalid sec filter comparator.

Action:
Choose correct comparator, GRANTED.

ESS-08002
Invalid value passed to "name" of RuntimeDataPermission: {0}. Please check the server logs.

Category:
Other

Cause:
Invalid value passed to 'name' of RuntimeDataPermission

Action:
Provide the correct permission name.

ESS-08003
Unsupported query field {0} specified in RuntimeDataPermission name Please check the server logs.

Category:
Other

Cause:
Unsupported query field name passed to 'name' of RuntimeDataPermission

Action:
Provide a valid queryField in permission name.

ESS-09000
Translation service with resource bundles {0} for Locale {1} can not be performed due to runtime error.

Category:
Programmatic

Cause:
ESS runtime encountered a failure for the given translation request.

Action:
Correct the bundle id, make sure it exists in the application environement.

ESS-09001
Message with requested key {0} is not found in the associated resource bundles.

Category:
Programmatic

Cause:
Message with the requested key is not found in the resource bundle.

Action:
Make sure the key is entered correctly.

ESS-09002
{0} is not a valid {1} implementation.

Category:
Programmatic

Cause:
The implementation class is not of expected interface type.

Action:
Make sure the implementation class implements the proper interface.

ESS-09003
Failed to instantiate the translation service factory implementation {0}.

Category:
Programmatic

Cause:
Error while instantiating an instance of translation service factory.

Action:
Check the log to find exception details.

ESS-09004
Failed to retrieve a valid instance of underlying oracle.javatools ResourceBundleManager. Design time metadata translation is not supported.

Category:
Programmatic

Cause:
Error while instantiating an instance of oracle.javatools.resourcebundle.ResourceBundleManager.

Action:
None

ESS-09005
Encountered MDS exception while performing MDS operations.

Category:
Programmatic

Cause:
Encountered MDS exception.

Action:
Check the exception for details.

ESS-09400
Encountered an execution context exception.

Category:
Programmatic

Cause:
Encountered exception while invoking DMS execution context API(s).

Action:
Check exception stack trace for details.

ESS-09402
Failed to compile recurrence expression.

Category:
Programmatic

Cause:
Failed to compile recurrence expression

Action:
Correct the invalid recurrence expression.

ESS-09403
Schedule list limit must be a non-negative integer.

Category:
Programmatic

Cause:
Schedule List limit is invalid.

Action:
List limit must be a non-negative integer.

ESS-09404
Schedule list begin date cannot be null.

Category:
Programmatic

Cause:
Invalid Null Schedule Begin date.

Action:
Provide a non-null begin date for the schedule.

ESS-09405
Schedule begin date can not be after end date.

Category:
Programmatic

Cause:
Begin Date for the schedule is after the end date.

Action:
Correct the invalid begin date or end date.

ESS-09406
Parsing exception. Only one day type recurrence field may be specified.

Category:
Programmatic

Cause:
More than one of BYDAY, BYMONTHDAY, BYYEARDAY was specified

Action:
Correct the invalid recurrence.

ESS-09407
Parsing exception. An occurrence by week number can only be used with a yearly frequency.

Category:
Programmatic

Cause:
A BYWEEKNO clause was specified with a frequency other than YEARLY

Action:
Correct the invalid recurrence.

ESS-09408
Parsing exception. An occurrence by week number cannot be used with an occurrence by month.

Category:
Programmatic

Cause:
More than one of BYWEEKNO, BYMONTH was specified

Action:
Correct the invalid recurrence.

ESS-09409
Parsing exception. Recurrence expression with {0} clause is not supported.

Category:
Programmatic

Cause:
One of the recurrence rule BYSETPOS, UNTIL, COUNT, WKST was specified

Action:
Correct the unsupported Recurrence Expression.

ESS-09410
Parsing exception. Value for {0} clause is out of range.

Category:
Programmatic

Cause:
Out of range value for recurrence rule was specified

Action:
Correct the invalid recurrence.

ESS-09411
Parsing exception. {0} clause is redundant in the recurrence expression.

Category:
Programmatic

Cause:
Redundant recurrence rule was specified

Action:
Correct the invalid recurrence.

ESS-09412
Recurrence expression is not valid. Please verify clauses and that each clause, including the last one, is followed by a semicolon.

Category:
Programmatic

Cause:
Invalid recurrence expression was specified.

Action:
Correct the invalid recurrence and verify that it should be followed by a semicolon at the end of the expression.

ESS-09420
Property {0} is not set for request {1}.

Category:
Programmatic

Cause:
A system property that should have been set has not been set.

Action:
Contact Oracle Support Services.

ESS-09421
Request {0} is not eligible to be manually recovered until {1}.

Category:
Programmatic

Cause:
The request is not yet eligible to be recovered.

Action:
Wait until the prescribed time to attempt this operation.

ESS-09422
A hard cancel must be attempted on PL/SQL request {0} before a force cancel is allowed.

Category:
Programmatic

Cause:
A hard cancel of this request must be attempted before trying a force cancel.

Action:
Cancel the request using the old-style hard cancel.

10
FRC-60003 to FRC-60108

FRC-60003
error reading ORACLE_HOME registry file {0}

Category:
Configuration

Cause:
An error occurred while reading the ORACLE_HOME registry file.

Action:
Do one of the following: \n1. Make sure that the ORACLE_HOME registry file exists. \n2. If the ORACLE_HOME registry file is accidentally deleted or modified then reinstall ORACLE_HOME.

FRC-60004
I/O error reading CA preferences file {0}

Category:
Configuration

Cause:
An I/O error occurred while reading the CA preferences file.

Action:
Examine the stack trace that accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRC-60101
error converting the configuration object to the relevant CompositeType

Category:
Configuration

Cause:
Failed to convert the configuration object to the relevant CompositeType.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRC-60102
error converting the configuration object to the relevant CompositeData

Category:
Configuration

Cause:
Failed to convert the configuration object to the relevant CompositeData.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRC-60103
error registering child config mbean for the application section {0}

Category:
Configuration

Cause:
Failed to register the child config mbean for the given application section.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it.

FRC-60104
error deregistering child config mbean for the application section {0}

Category:
Configuration

Cause:
Failed to deregister the child config mbean for the given application section.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it.

FRC-60105
error deleting application section {0}

Category:
Configuration

Cause:
An attempt was made to delete the default application section or a section that does not exist.

Action:
Choose the correct section name.

FRC-60106
error creating application section {0}

Category:
Configuration

Cause:
An attempt was made to create an application section that already exists or has an invalid section name.

Action:
Choose an alternative name for the section.

FRC-60107
error duplicating application section {0} to {1}

Category:
Configuration

Cause:
Failed to duplicate an application section because of one of the following reasons:\n 1. An attempt was made to duplicate an invalid application section.\n 2. An attempt was made to create an application section that already exists.

Action:
Do one of the following:\n 1. Choose a correct section name for the duplicated application section.\n 2. Choose an alternative name for the newly created application section.

FRC-60108
error processing configuration, invalid entry at line:{0}

Category:
Configuration

Cause:
An unexpected error occurred while persisting the configuration.

Action:
Fix the configuration and submit it again.

11

FRM-41480 to FRM-99999

FRM-41480
error in FSCRATCHPAD.EXPAND_TEMPLATE: syntax error in URI template {0} at offset {1} [characters]

Category:
Data

Cause:
The URI template specified by the 'uri_template' parameter passed to FSCRATCHPAD.EXPAND_TEMPLATE was not syntactically correct [RFC 6570, level 4].

Action:
Correct the URI template.

FRM-41484
error in FSCRATCHPAD.EXPAND_TEMPLATE: "parameters" contains an element of unexpected type; its JSON pointer is {0}

Category:
Data

Cause:
The values of the children of the JSON object specified by the 'parameters' parameter passed to FSCRATCHPAD.EXPAND_TEMPLATE must be strings, arrays of strings, or objects whose child values are strings or arrays of strings. A violation of this constraint was detected.

Action:
Correct the offending element.

FRM-41486
error in FSCRATCHPAD.EXPAND_TEMPLATE: "parameters" contains an element with an object key containing an invalid %-encoding; the element"s JSON pointer is {0}

Category:
Data

Cause:
A child element of the JSON object specified by the 'parameters' parameter passed to FSCRATCHPAD.EXPAND_TEMPLATE corresponded to a variable in a '+' or '#' expression in the URI template specified by the 'uri_template' parameter, and the object key of the child element or an element within it contained an invalid sequence of 3-byte %-encodings. Each %-encoding must consist of '%' followed by 2 hex digits, and the sequence of bytes denoted by the %-encodings must be a valid AL32UTF8 representation of a Unicode character.

Action:
Correct the offending element.

FRM-41487
error in FSCRATCHPAD.EXPAND_TEMPLATE: "parameters" contains a STRING element with a value containing an invalid %-encoding; the element"s JSON pointer is {0}

Category:
Data

Cause:
A child element of the JSON object specified by the 'parameters' parameter passed to FSCRATCHPAD.EXPAND_TEMPLATE corresponded to a variable in a '+' or '#' expression in the URI template specified by the 'uri_template' parameter, and the value of the child element or an element within it contained an invalid sequence of 3-byte %-encodings. Each %-encoding must consist of '%' followed by 2 hex digits, and the sequence of bytes denoted by the %-encodings must be a valid AL32UTF8 representation of a Unicode character.

Action:
Correct the offending element.

FRM-41492
error in runtime process: FSCRATCHPAD contents or FJSON string value not a valid base64 encoding: invalid byte detected at offset {0} [bytes]

Category:
Data

Cause:
'base64_decode := true' was specified for FSCRATCHPAD.TO_FILE or FJSON.STRING_VALUE_TO_FILE, but the scratchpad contents (up to the string specified by the 'stop_at' parameter, if specified) or the JSON string value did not constitute a valid base64 encoding. A valid base64 encoding must contain only white space [blank, tab, carriage return, or line feed] or base64 alphabet characters ['A'-'Z', 'a'-'z', '0'-'9', '+', '/', or '=']. '=' characters are not required, but if present, they must occur only at the end, and they must ensure that the total number of base64 alphabet characters is a multiple of 4. If the invalid base64 encoding was obtained from a string element retrieved from a REST endpoint, a subsequent FRM-41592 provides the offending string element's JSON pointer.

Action:
Correct application logic that populates the scratchpad.

FRM-41493
error in runtime process: FSCRATCHPAD contents or FJSON string value could not be written to {0}

Category:
Files

Cause:
FSCRATCHPAD.TO_FILE or FJSON.STRING_VALUE_TO_FILE was unable to successfully write the contents to the location specified by the 'file_name' parameter.

Action:
Verify that the file name is spelled correctly and that the application has permission to write a file to the specified directory, and that the specified directory has adequate space.

FRM-41494
error in runtime process: could not find file {0} for FSCRATCHPAD or FJSON package

Category:
Files

Cause:
The 'file_name' parameter passed to FSCRATCHPAD.APPEND_FILE or FJSON.NEW_STRING_FROM_FILE specified a file that could not be found.

Action:
Verify that the file name is spelled correctly and that the application has permission to read the file.

FRM-41495
error in runtime process: error reading file {0} for FSCRATCHPAD or FJSON package

Category:
Files

Cause:
The 'file_name' parameter passed to FSCRATCHPAD.APPEND_FILE or FJSON.NEW_STRING_FROM_FILE specified a file that could not be read successfully.

Action:
Verify that the file name is spelled correctly and that the application has permission to read the file.

FRM-41516
loop in JSON parse tree

Category:
Data

Cause:
Application design error. An attempt to produce a JSON pointer for a diagnostic message detected a loop in the JSON parse tree [so it wasn't really a tree at all]: the root of the JSON parse tree was encountered while traversing its descendent elements. The production of the JSON pointer was aborted and the memory it consumed was released. The JSON pointer is shown as '?' in the diagnostic message. This condition was caused by an earlier call to FJSON.ADD, FJSON.SET, or FJSON.PUT that added a child element C to an array or object A, where C was equal to A or was an ancestor of A.

Action:
Correct the application logic.

FRM-41530
error in runtime process: {0} was passed an unexpected retrieved {1} {2}; its JSON pointer was {3}

Category:
Data

Cause:
Application design error. An FJSON.ELEMENT_T value retrieved from a REST endpoint was passed as the first parameter to a function or procedure in the FJSON package or as the second parameter to the POPULATE_GROUP_FROM_JSON procedure, and specified an element whose element type is not supported by the specified function or procedure. An FJSON.CONTENT exception was raised (except for POPULATE_GROUP_FROM_JSON). Additional information was written to ODL, starting with FRM-41539.

Action:
Correct the application logic.

FRM-41531
error in runtime process: unexpected retrieved {0} element found by {1}, which was passed a {2} whose JSON pointer was {3}, and a {4} whose value was {5}

Category:
Data

Cause:
Application design error. An FJSON.FIND_x or FJSON.GET_x function produced an element of an unexpected type that was retrieved from a REST endpoint. An FJSON.CONTENT exception was raised. Additional information was written to ODL, starting with FRM-41539.

Action:
Correct the application logic.

FRM-41532
error in runtime process: no element found where expected by {0}, which was passed a retrieved {1} whose JSON pointer was {2}, and a {3} whose value was {4}

Category:
Data

Cause:
Application design error. An FJSON.FIND_ARRAY, FJSON.FIND_OBJECT, FJSON.GET_ARRAY, or FJSON.GET_OBJECT function produced no element, and the FJSON.ELEMENT_T value passed as the first parameter to the function was retrieved from a REST endpoint. An FJSON.CONTENT exception was raised. Additional information was written to ODL, starting with FRM-41539.

Action:
Correct the application logic.

FRM-41533
error in runtime process: {0} was passed a {1} that contained an unexpected {2} element whose JSON pointer was {3}

Category:
Data

Cause:
Application design error. One of the following occurred:\n1. The JSON array passed as the first parameter to the FJSON.JOIN function contained an element that was not a JSON string.\n2. The JSON array or JSON object passed as the second parameter to the POPULATE_GROUP_FROM_JSON function contained an initial element that was a JSON object, but also contained an element that was not a JSON object.\n3. The JSON array or JSON object passed as the second parameter to the POPULATE_GROUP_FROM_JSON function contained an initial element that was a JSON array or scalar element, but also contained an element that was a JSON object.\n4. The JSON array or JSON object passed as the second parameter to the POPULATE_GROUP_FROM_JSON function contained a scalar element, or a JSON array or JSON object that in turn contained a scalar element, and the type of the scalar element did not match the corresponding record group column. [DATE columns are a special case: if a null epoch_unit was passed to POPULATE_GROUP_FROM_JSON, the corresponding scalar element must be a JSON string (representing an ISO 8601 date/time string); otherwise, it must be a JSON number (representing "epoch": seconds since 1970-01-01).]\nIn case 1, an FJSON.CONTENT exception was raised.\nIf the offending element was retrieved from a REST endpoint, additional information was written to ODL, starting with FRM-41539.

Action:
Correct the application logic.

FRM-41534
error in runtime process: {0} was passed a {1} that contained a {2} element whose JSON pointer was {3}. The element was expected to represent a date, but an ORA-0{4} exception was encountered when the conversion to date was attempted.

Category:
Data

Cause:
Application design error. The JSON array or JSON object passed as the second parameter to the POPULATE_GROUP_FROM_JSON function contained a scalar element, or a JSON array or JSON object that in turn contained a scalar element, and the corresponding record group column was of type DATE. Either a null epoch_unit was passed to POPULATE_GROUP_FROM_JSON and the scalar element was a JSON string which was not in valid ISO 8601 format, or a non-null epoch_unit was specified and the scalar element was a JSON number which was not a valid epoch. If the exception was not ORA-06502 and the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 2 or more, the offending value is displayed [FRM-41537]. If the offending element was retrieved from a REST endpoint, additional information was written to ODL, starting with FRM-41539.

Action:
Correct the application logic.

FRM-41535
error in runtime process: {0} was passed a {1} that contained a STRING element whose value was unexpectedly too large. The full JSON pointer was {2}

Category:
Data

Cause:
Application design error. The JSON array or JSON object passed as the second parameter to the POPULATE_GROUP_FROM_JSON function contained a JSON string element, or a JSON array or JSON object that in turn contained a JSON string element, and the value of the string element exceeded 32767 bytes. If the offending element was retrieved from a REST endpoint, additional information was written to ODL, starting with FRM-41539.

Action:
Correct the application logic.

FRM-41536
error in runtime process: {0} was passed a {1} that contained an element whose object key was unexpectedly too large, or was not (when expected) a valid number. The full JSON pointer was {2}

Category:
Data

Cause:
Application design error. A JSON object was passed as the second parameter to the POPULATE_GROUP_FROM_JSON function. It contained an element whose object key exceeded 32767 bytes or, in the case where the first record group column was of type NUMBER, could not be converted to a number. If the offending element was retrieved from a REST endpoint, additional information was written to ODL, starting with FRM-41539.

Action:
Correct the application logic.

FRM-41537
The value which could not be converted was {0}

Category:
Data

Cause:
This message follows FRM-41534 and displays the offending value if the exception was not ORA-06502 and the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 2 or more.

Action:
No action is required.

FRM-41539
The unexpected JSON content was produced by a {0} request to the URL generated from the URI template {1}

Category:
Data

Cause:
This message provides additional information about unexpected JSON content in the JSON text response from a REST endpoint. It may be followed by a dump of the request and the response [FRM-41690 and FRM-41691], depending on the value of the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable.

Action:
No action is required.

FRM-41540
error in runtime process: unexpected content detected in JSON document: {0}

Category:
Data

Cause:
The application called the FJSON.UNEXPECTED_CONTENT procedure with a null target element, presumably because its logic detected unexpected content of some sort. An FJSON.CONTENT exception was raised.

Action:
Try to determine what is producing the unexpected JSON content, e.g. by contacting the owner of the REST service from which the JSON document was retrieved. Correct application logic if necessary.

FRM-41541
error in runtime process: unexpected content detected in JSON document at {0}: {1}

Category:
Data

Cause:
The application called the FJSON.UNEXPECTED_CONTENT procedure with a non-null target element, presumably because its logic detected unexpected content of some sort. An

FJSON.CONTENT exception was raised. If the offending element was retrieved from a REST endpoint, additional information was written to ODL, starting with FRM-41539.

Action:
Try to determine what is producing the unexpected JSON content, e.g. by contacting the owner of the REST service from which the JSON document was retrieved. Correct application logic if necessary.

FRM-41549
error in runtime process: unexpected scalar conversion exception ORA-0{0} encountered while processing JSON document

Category:
Data

Cause:
The application called the FJSON.ANALYZE_EXCEPTION procedure within a PL/SQL exception block, and it tentatively determined that the exception could plausibly have been produced by a PL/SQL assignment from a scalar derived from a REST endpoint response, to a PL/SQL variable (or an assignment from that variable to another using a conversion function such as TO_DATE). An FJSON.CONTENT exception was raised. Additional information was written to ODL, starting with FRM-41550 or FRM-41551.

Action:
Try to determine what is causing the scalar conversion exception. It could be due to an application design error unrelated to the REST service; if so, correct the application logic. Otherwise, try to determine what is producing the unexpected JSON content, e.g. by contacting the owner of the REST service from which the JSON document was retrieved. Correct application logic if necessary.

FRM-41550
The last scalar-producing FJSON function executed prior to calling FJSON.ANALYZE_EXCEPTION was FJSON.{0}, with a {1} whose JSON pointer was {2}, and with a {3} whose value was {4}

Category:
Data

Cause:
This message follows FRM-41549 in the case where the last scalar-producing FJSON function was a "composite" function: get_string_value, get_number_value, get_boolean_value, find_string_value, find_number_value, find_boolean_value, or find_object_key. It specifies the arguments passed to the function: target object or array, and object key or array position.

Action:
No action is required.

FRM-41551
The last scalar-producing FJSON function executed prior to calling FJSON.ANALYZE_EXCEPTION was FJSON.{0}, with a {1} whose JSON pointer was {2}

Category:
Data

Cause:
This message follows FRM-41549 in the case where the last scalar-producing FJSON function was not a composite function. It specifies the JSON element passed to the function.

Action:
No action is required.

FRM-41552
The returned value was null, because no element was found.

Category:
Data

Cause:
This message follows FRM-41550 if the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 1 or more and the composite scalar-producing FJSON function found no element.

Action:
No action is required.

FRM-41553
The returned value was null, obtained from a {0} element.

Category:
Data

Cause:
This message follows FRM-41550 or FRM-41551 if the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 1 or more and the scalar-producing FJSON function found or was passed a NULL element or a STRING element whose value was the empty string.

Action:
No action is required.

FRM-41554
The returned value was {0}

Category:
Data

Cause:
This message follows FRM-41550 or FRM-41551 if the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 2 or more and the scalar-producing FJSON function found or was passed a BOOLEAN element, a NUMBER element, or a STRING element whose value was non-empty and whose AL32UTF8 representation did not exceed 4095 bytes.

Action:
No action is required.

FRM-41555
The returned value was a non-null VARCHAR2 containing {0} characters and {1} bytes (in the NLS_LANG charset: {2}).

Category:
Data

Cause:
This message follows FRM-41550 or FRM-41551 if the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 1 and the scalar-

producing FJSON function found or was passed a STRING element whose value was non-empty, or if FORMS_HTTP_DIAGNOSTIC_LEVEL is set to 2 or more and the scalar-producing FJSON function found or was passed a STRING element whose AL32UTF8 representation exceeded 4095 bytes.

Action:
No action is required.

FRM-41556
The returned value was a non-null NUMBER{0} (when rounded to an integer).

Category:
Data

Cause:
This message follows FRM-41550 or FRM-41551 if the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 1 and the scalar-producing FJSON function found or was passed a NUMBER element. It indicates whether the value was zero, positive, or negative, and whether it would fit in a PLS_INTEGER.

Action:
No action is required.

FRM-41557
The returned value was a non-null BOOLEAN.

Category:
Data

Cause:
This message follows FRM-41550 or FRM-41551 if the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 1 and the scalar-producing FJSON function found or was passed a BOOLEAN element.

Action:
No action is required.

FRM-41560
error in runtime process: syntax error in retrieved JSON text at offset {0} [bytes]

Category:
Data

Cause:
A parse of the JSON text response from a REST endpoint encountered a violation of RFC 7159. The parse was aborted, and the memory that had already been allocated for the parse tree was made available for subsequent JSON parse tree operations. An FJSON.PARSE_FAILURE exception was raised. Additional information was written to ODL, starting with FRM-41569.

Action:
Try to determine why the erroneous JSON text is being returned, e.g. by contacting the owner of the REST service.

FRM-41561
error in runtime process: oversize object key in retrieved JSON text, ending at offset {0} [bytes]

Category:
Data

Cause:
A parse of the JSON text response from a REST endpoint encountered an oversize object key in an object member definition. By default, Oracle Forms does not support object keys whose AL32UTF8 representation exceeds 32767 bytes. [Larger keys cannot be used in PL/SQL VARCHAR2 variables.] The parse was aborted, and the memory that had already been allocated for the parse tree was made available for subsequent JSON parse tree operations. An FJSON.PARSE_FAILURE exception was raised. Additional information was written to ODL, starting with FRM-41569.

Action:

FRM-41562
error in runtime process: oversize array or object in retrieved JSON text, detected at offset {0} [bytes]

Category:
Data

Cause:
A parse of the JSON text response from a REST endpoint encountered an array or object which contained 2G elements or more. The parse was aborted, and the memory that had already been allocated for the parse tree was made available for subsequent JSON parse tree operations. An FJSON.PARSE_FAILURE exception was raised. Additional information was written to ODL, starting with FRM-41569.

Action:
Try to determine why the oversize array or object is being returned, e.g. by contacting the owner of the REST service.

FRM-41569
The JSON text which could not be parsed was produced by a {0} request to the URL generated from the URI template {1}

Category:
Data

Cause:
This message provides additional information about a parse error in the JSON text response from a REST endpoint. It may be followed by a dump of the request and the response [FRM-41690 and FRM-41691], depending on the value of the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable.

Action:
No action is required.

FRM-41570
error in runtime process: JSON parse memory limit exceeded

Category:
Memory

Cause:
A parse of the JSON text response from a REST endpoint required more memory than the JSON parse memory limit (4Gb or the limit specified by the

FORMS_JSON_PARSE_MEMORY_LIMIT environment variable). The parse was aborted, and the memory that had already been allocated for the parse tree was made available for subsequent JSON parse tree operations. An FJSON.PARSE_ALLOCATION exception was raised.

Action:
Modify the selection criteria specified in the request to the REST endpoint, so as to limit the size of the response, or increase the value of the FORMS_JSON_PARSE_MEMORY_LIMIT environment variable.

FRM-41571
error in runtime process: JSON new memory limit exceeded

Category:
Memory

Cause:
An attempt to programmatically create a JSON element (using e.g. FJSON.CLONE or an FJSON.NEW_x function) would have caused the memory consumed by all programmatically created JSON elements to exceed the new memory limit (4Gb or the limit specified by the FORMS_JSON_NEW_MEMORY_LIMIT environment variable). An FJSON.GLOBAL_ALLOCATION exception was raised.

Action:
Revise application logic so as to programmatically create fewer JSON elements, or increase the value of the FORMS_JSON_NEW_MEMORY_LIMIT environment variable.

FRM-41572
error in runtime process: JSON memory allocation failed

Category:
Memory

Cause:
An operation to create, update, or generate a JSON parse tree was unable to allocate adequate memory. An FJSON.GLOBAL_ALLOCATION exception was raised..

Action:
Modify the selection criteria specified in the request to the REST endpoint, so as to limit the size of the response, or revise application logic so as to programmatically create fewer JSON elements.

FRM-41573
error in runtime process: JSON parse trees require excessive memory for element values

Category:
Memory

Cause:
This error arises only if both the following occur:\n1. The FORMS_JSON_KEY_LENGTH_BITS environment variable [which defaults to 15, limiting object keys to 32767 bytes] was set to a value N in the range 16..30 [the maximum allowed].\n2. The total number of bytes required for all strings, numbers, and hash arrays for all elements in all JSON parse trees exceeded 2 raised to the power of 64-N.\nIf this error occurred, then an FJSON.GLOBAL_ALLOCATION exception was raised.

Action:
Modify the selection criteria specified in the request to the REST endpoint, so as to limit the size of the response, or revise application logic so as to programmatically create fewer JSON elements.

FRM-41574
error in runtime process: too many elements in JSON parse trees

Category:
Memory

Cause:
An operation to create or update a JSON parse tree would have caused the total number of elements in all JSON parse trees to equal or exceed 4G. An FJSON.GLOBAL_ALLOCATION exception was raised.

Action:
Modify the selection criteria specified in the request to the REST endpoint, so as to limit the size of the response, or revise application logic so as to programmatically create fewer JSON elements.

FRM-41580
error in runtime process: invalid $ref string {0} in element at {1}: syntax error at offset {2} [characters]

Category:
Data

Cause:
The element passed to FJSON.RESOLVE$REF specified a $ref string which was not a syntactically valid URI.

Action:
Contact the provider of the service which produced the document containing the invalid JSON reference.

FRM-41581
error in runtime process: loop or overflow in recursive JSON references: {0}

Category:
Data

Cause:
The element passed to FJSON.RESOLVE$REF specified a $ref string which resolved to another $ref element, which in turn resolved to yet another $ref element, and so forth. The chain of recursive references, shown in the diagnostic message, contained a loop or more than 16 entries.

Action:
Contact the provider of the service which produced the document containing the invalid JSON reference.

FRM-41582
error in runtime process: $ref string {0} in element at {1} specifies a document which cannot be loaded: the $ref string itself resides in a document which was not loaded from a URL

Category:
Data

Cause:

Action:
Correct application logic. In general, $ref strings should not be placed in programmatically constructed documents.

FRM-41583
error in runtime process: $ref string {0} in element at {1} specifies a document which could not be loaded and parsed: an error occurred on the internal call to FHTTP.ISSUE_REQUEST

Category:
Data

Cause:
Self-explanatory

Action:
Examine the error messages that were produced for the internal call to FHTTP.ISSUE_REQUEST.

FRM-41584
error in runtime process: JSON pointer {0} could not be evaluated against document {1}: syntax error at offset {2} [characters]

Category:
Data

Cause:
Either (1) an invalid JSON pointer was passed to FJSON.EVALUATE_POINTER, or (2) the element passed to an invocation of FJSON.RESOLVE$REF specified a $ref string whose fragment [the portion after the '#'] was not a valid JSON pointer. The JSON pointer did not begin with '/' or contained an invalid escape sequence ['~' not followed by '0' or '1'].

Action:
In case (1), correct the application logic. In case (2), contact the provider of the service which produced the document containing the invalid JSON reference.

FRM-41585
error in runtime process: JSON pointer {0} could not be evaluated against document {1}: element specified by portion preceding '/' at offset {2} [characters] is not an object or array

Category:
Data

Cause:
Either (1) an invalid JSON pointer was passed to FJSON.EVALUATE_POINTER, or (2) the element passed to an invocation of FJSON.RESOLVE$REF specified a $ref string whose fragment [the portion after the '#'] was not a valid JSON pointer. The JSON pointer contained a '/' at the specified offset, but the portion of the specified JSON pointer preceding that '/' specified a scalar JSON element.

Action:
In case (1), correct the application logic. In case (2), contact the provider of the service which produced the document containing the invalid JSON reference.

FRM-41586
error in runtime process: JSON pointer {0} could not be evaluated against document {1}: key specified after "/" at offset {2} [characters] does not exist in the object specified by portion preceding the "/"

Category:
Data

Cause:
Either (1) an invalid JSON pointer was passed to FJSON.EVALUATE_POINTER, or (2) the element passed to an invocation of FJSON.RESOLVE$REF specified a $ref string whose fragment [the portion after the '#'] was not a valid JSON pointer. The JSON pointer contained a '/' at the specified offset, and the portion of the specified JSON pointer preceding that '/' specified an object, but that object did not contain the key specified after the '/'.

Action:
In case (1), correct the application logic. In case (2), contact the provider of the service which produced the document containing the invalid JSON reference.

FRM-41587
error in runtime process: JSON pointer {0} could not be evaluated against document {1}: invalid array index specified after "/" at offset {2} [characters]

Category:
Data

Cause:
Either (1) an invalid JSON pointer was passed to FJSON.EVALUATE_POINTER, or (2) the element passed to an invocation of FJSON.RESOLVE$REF specified a $ref string whose fragment [the portion after the '#'] was not a valid JSON pointer. The JSON pointer contained a '/' at the specified offset, and the portion of the specified JSON pointer preceding that '/' specified an array, but the array index specified after the '/' was not a valid nonnegative decimal number.

Action:
In case (1), correct the application logic. In case (2), contact the provider of the service which produced the document containing the invalid JSON reference.

FRM-41588
error in runtime process: JSON pointer {0} could not be evaluated against document {1}: array index specified after "/" at offset {2} [characters] does not fall within the array specified by portion preceding the "/"

Category:
Data

Cause:
Either (1) an invalid JSON pointer was passed to FJSON.EVALUATE_POINTER, or (2) the element passed to an invocation of FJSON.RESOLVE$REF specified a $ref string whose fragment [the portion after the '#'] was not a valid JSON pointer. The JSON pointer contained a '/' at the specified offset, and the portion of the specified JSON pointer preceding that '/' specified an array, but that array did not contain the element specified by the 0-relative index after the '/'.

Action:
In case (1), correct the application logic. In case (2), contact the provider of the service which produced the document containing the invalid JSON reference.

FRM-41592
The invalid base64 encoding was obtained from a STRING element whose JSON pointer was {0}

Category:
Data

Cause:
This message provides additional information about an invalid base64 encoding [reported in a preceding FRM-41492] in the JSON text response from a REST endpoint. It may be followed by a dump of the request and the response [FRM-41690 and FRM-41691], depending on the value of the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable.

Action:
No action is required.

FRM-41610
error in FHTTP.ISSUE_REQUEST: the {0} method sent to the URL generated from the URI template {1}{2} was rejected.

Category:
Requests/Responses

Cause:
The method specified by the 'method' parameter passed to FHTTP.ISSUE_REQUEST was rejected. This can happen if a security manager is set and the method is 'TRACE', but the 'allowHttpTrace' NetPermission is not granted.

Action:
Determine whether the conditions above apply. If not, and the problem persists, contact Oracle Support Services.

FRM-41620
error in FHTTP.ISSUE_REQUEST: server URL could not be obtained due to invalid "server_url_or_id" parameter {0}.

Category:
Data

Cause:
The 'server_url_or_id' parameter passed to FHTTP.ISSUE_REQUEST must begin with 'http:', 'https:', 'ws:', or 'wss:', or else must contain only alphanumeric characters and '_', '.', '-'.

Action:
Correct the 'server_url_or_id' parameter.

FRM-41621
error in FHTTP.ISSUE_REQUEST: server URL could not be obtained due to invalid config section name {0}

Category:
Data

Cause:
If a non-null 'server_url_or_id' parameter is passed to FHTTP.ISSUE_REQUEST, and it does not begin with 'http:', 'https:', 'ws:', or 'wss:', the config section name specified as the config

parameter in the frmservlet URL used to launch the Forms application must contain only alphanumeric characters and '_', '.', '-'.

Action:
Specify a config section with a valid name in the frmservlet URL used to launch the Forms application.

FRM-41622
error in FHTTP.ISSUE_REQUEST: server URL could not be obtained due to missing credential for {0}

Category:
Configuration

Cause:
If a non-null 'server_url_or_id' parameter is passed to FHTTP.ISSUE_REQUEST, and it does not begin with 'http:', 'https:', 'ws:', or 'wss:', the Oracle Platform Security Services Credential Store must contain a generic credential for the server. The credential key must be of the form <config_section_name>=<credential_id>.

Action:
Use Fusion Middleware Control to add the generic credential. The value must be a well-formed URL which specifies a scheme of 'http', 'https', 'ws', or 'wss'.

FRM-41623
error in FHTTP.ISSUE_REQUEST: the server URL {1} specified by the credential for {0} was rejected.

Category:
Configuration

Cause:
If a non-null 'server_url_or_id' parameter is passed to FHTTP.ISSUE_REQUEST, and it does not begin with 'http:', 'https:', 'ws:', or 'wss:', the Oracle Platform Security Services Credential Store must contain a generic credential for the server. The credential key must be of the form <config_section_name>=<credential_id>. The value must be a string that's a well-formed URL which specifies a scheme of 'http', 'https', 'ws', or 'wss'.

Action:
Use Fusion Middleware Control to correct the generic credential.

FRM-41624
error in FHTTP.ISSUE_REQUEST: the server URL {1} was rejected.

Category:
Configuration

Cause:
The 'server_url_or_id' parameter passed to FHTTP.ISSUE_REQUEST began with 'http:', 'https:', 'ws:', or 'wss:', but it was not a well-formed URL.

Action:

FRM-41630
error in FHTTP.ISSUE_REQUEST: syntax error in URI template {0} at offset {1} [characters]

Category:
Data

Cause:
The URI template specified by the 'uri_template' parameter passed to FHTTP.ISSUE_REQUEST was not syntactically correct [RFC 6570, level 4].

Action:
Correct the URI template.

FRM-41633
error in FHTTP.ISSUE_REQUEST: the URL generated from the URI template {0}{1} for a {2} request was rejected.

Category:
Data

Cause:
The URL generated from the 'uri_template' and 'url_parameters' parameters passed to FHTTP.ISSUE_REQUEST was malformed or, if the 'server_url_or_id' parameter was null or not specified, did not specify a scheme of 'http', 'https', 'ws', or 'wss'.

Action:
Correct the 'uri_template' and/or 'url_parameters' parameters.

FRM-41640
error in FHTTP.ISSUE_REQUEST: "url_parameters" contains an unexpected {0} element; its JSON pointer is {1}

Category:
Data

Cause:
The values of the children of the JSON object specified by the 'url_parameters' parameter passed to FHTTP.ISSUE_REQUEST must be strings, arrays of strings, or objects whose child values are strings or arrays of strings. A violation of this constraint was detected.

Action:
Correct the offending element.

FRM-41642
error in FHTTP.ISSUE_REQUEST: "url_parameters" contains an element with an object key containing an invalid %-encoding; the element"s JSON pointer is {0}

Category:
Data

Cause:
A child element of the JSON object specified by the 'url_parameters' parameter passed to FHTTP.ISSUE_REQUEST corresponded to a variable in a '+' or '#' expression in the URI template specified by the 'uri_template' parameter, and the object key of the child element or an element within it contained an invalid sequence of 3-byte %-encodings. Each %-encoding must consist of '%' followed by 2 hex digits, and the sequence of bytes denoted by the %-encodings must be a valid AL32UTF8 representation of a Unicode character.

Action:
Correct the offending element.

FRM-41643
error in FHTTP.ISSUE_REQUEST: "url_parameters" contains a STRING element with a value containing an invalid %-encoding; the element"s JSON pointer is {0}

Category:
Data

Cause:
A child element of the JSON object specified by the 'url_parameters' parameter passed to FHTTP.ISSUE_REQUEST corresponded to a variable in a '+' or '#' expression in the URI template specified by the 'uri_template' parameter, and the value of the child element or an element within it contained an invalid sequence of 3-byte %-encodings. Each %-encoding must consist of '%' followed by 2 hex digits, and the sequence of bytes denoted by the %-encodings must be a valid AL32UTF8 representation of a Unicode character.

Action:
Correct the offending element.

FRM-41650
error in FHTTP.ISSUE_REQUEST: "request_headers" contains an unexpected {0} element; its JSON pointer is {1}

Category:
Data

Cause:
The values of the children of the JSON object specified by the 'request_headers' parameter passed to FHTTP.ISSUE_REQUEST must be strings. A violation of this constraint was detected.

Action:
Correct the offending element.

FRM-41652
error in FHTTP.ISSUE_REQUEST: "request_headers" contains an element whose object key is not a valid HTTP header name: invalid character found at offset {0} [characters]; the element"s JSON pointer is {1}

Category:
Data

Cause:
The object key of a child of the JSON object specified by the 'request_headers' parameter passed to FHTTP.ISSUE_REQUEST did not conform to the syntax for a header name specified by RFC 7230: an invalid character was found. Characters in header values must be visible USASCII characters [0x21-0x7f], and must not be any of: '"', '(', ')', ',', '/', ':', ';', '<', '=', '>', '?', '@', '[', '', ']', '{', '}'.

Action:
Correct the offending element.

FRM-41653
error in FHTTP.ISSUE_REQUEST: "request_headers" contains an element whose value is not a valid HTTP header value: invalid character found at offset {0} [characters]; the element"s JSON pointer is {1}

Category:
Data

Cause:
The value of a child of the JSON object specified by the 'request_headers' parameter passed to FHTTP.ISSUE_REQUEST did not conform to the syntax for a header value specified by RFC 7230: an invalid character was found. Characters in header values must be visible, or space, or horizontal tab. If the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 3 or 4, the invalid value is displayed in a subsequent FRM-41654 message.

Action:
Correct the offending element.

FRM-41654
The invalid header value is {0}

Category:
Data

Cause:
This message follows FRM-41653 if the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 3 or 4.

Action:
No action is required.

FRM-41660
error in FHTTP.ISSUE_REQUEST: a {0} request to the URL generated from the URI template {1}{2} encountered an error communicating with the external service.

Category:
Network

Cause:
The request issued by FHTTP.ISSUE_REQUEST encountered an IOException while attempting to communicate with the external service. A subsequent FRM-41692 message indicates where the stack trace for the IOException was written.

Action:
Inspect the stack trace in the response identified by message FRM-41692 in ODL. If the stack trace does not indicate how to fix the problem, and the problem persists, contact the owner of the external service.

FRM-41661
error in FHTTP.ISSUE_REQUEST: a {0} request to the URL generated from the URI template {1}{2} received unexpected response status code {3}.

Category:
Requests/Responses

Cause:
The request issued by FHTTP.ISSUE_REQUEST received a response status code that was not specified in the 'accept' parameter and was not one of the status codes that are always accepted, namely 200, and [for all methods except TRACE] 204, and [for PUT and POST] 201 and 205. A subsequent FRM-41691 message indicates where the body of the response was written.

Action:
If the status code is a legitimate response from the accessed external service, include it in the 'accept' parameter, and add appropriate logic to handle it. Otherwise, inspect the diagnostic information in the response identified by message FRM-41691 in ODL.

FRM-41671
error in FHTTP.ISSUE_REQUEST: the runtime process encountered a memory allocation failure while attempting to process a {0} request to the URL generated from the URI template {1}{2}

Category:

Cause:
FHTTP.ISSUE_REQUEST was unable to allocate adequate memory in the runtime process.

Action:
Specify fewer or smaller request headers or a smaller request body, or modify the selection criteria specified in the request to the external service, so as to limit the size of the response.

FRM-41672
error in FHTTP.ISSUE_REQUEST: WebLogic was unable to create a thread to process a request to an external service.

Category:
Threads

Cause:
The number of active threads created by the WebLogic server exceeded the limit specified by the <max-concurrent-new-threads> element in weblogic-application.xml, weblogic.xml, or config.xml, as described in 'Configuring Concurrent Managed Objects' in 'Oracle Fusion Middleware Administering Server Environments for Oracle WebLogic Server'. The Forms application was terminated.

Action:
Increase the limit or run the Forms application when the system is less heavily loaded.

FRM-41673
error in FHTTP.ISSUE_REQUEST: the JVM encountered an OutOfMemoryError while attempting to process a {0} request to the URL generated from the URI template {1}{2}

Category:
Memory

Cause:
FHTTP.ISSUE_REQUEST was unable to allocate adequate memory in the JVM that's issuing the request.

Action:
Specify fewer or smaller request headers or a smaller request body, or modify the selection criteria specified in the request to the external service, so as to limit the size of the response.

FRM-41674
error in Dynamic Monitoring Service (DMS): WebLogic was unable to create a thread to remove unused DMS objects.

Category:
Threads

Cause:
The number of active threads created by the WebLogic server exceeded the limit specified by the <max-concurrent-new-threads> element in weblogic-application.xml, weblogic.xml, or config.xml, as described in 'Configuring Concurrent Managed Objects' in 'Oracle Fusion Middleware Administering Server Environments for Oracle WebLogic Server'.

Action:
No action is necessary if this happens very rarely. Increase the limit if this happens frequently.

FRM-41675
error in Forms prestart processing: WebLogic was unable to create a thread to fill the pool of prestarted Forms runtime processes.

Category:
Threads

Cause:
The number of active threads created by the Weblogic server exceeded the limit specified by the <max-concurrent-new-threads> element in weblogic-application.xml, weblogic.xml, or config.xml, as described in 'Configuring Concurrent Managed Objects' in 'Oracle Fusion Middleware Administering Server Environments for Oracle WebLogic Server'.

Action:
No action is necessary if this happens very rarely. Increase the limit if this happens frequently.

FRM-41690
The reconstructed request line, request headers, and request body (if any) have been written to {0}

Category:
Requests/Responses

Cause:
This message follows FRM-41539, FRM-41569, FRM-41592, and various error messages written by FHTTP.ISSUE_REQUEST, if the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 3 or 4.

Action:
No action is required.

FRM-41691
The reconstructed response status line, response headers, and response body (if any) have been written to {0}

Category:
Requests/Responses

Cause:
This message follows FRM-41539 and FRM-41569, if the FORMS_HTTP_DIAGNOSTIC_LEVEL environment variable is set to 4, and various error messages written by FHTTP.ISSUE_REQUEST.

Action:
No action is required.

FRM-41692
The stack trace for the communication error has been written to {0}

Category:
Network

Cause:
This message follows FRM-41660 and FRM-41760.

Action:
No action is required.

FRM-41700
error encrypting credentials for an external service

Category:
Configuration

Cause:
An unexpected error occurred while encrypting credentials for an external service.

Action:
If the problem persists, contact Oracle Support Services.

FRM-41701
error decrypting credentials for an external service

Category:
Configuration

Cause:
An unexpected error occurred while decrypting credentials for an external service.

Action:
If the problem persists, contact Oracle Support Services.

FRM-41712
error in FHTTP.ISSUE_REQUEST: token {0} [{1}] missing from "authorization_info"

Category:
Data

Cause:
The 'authorization_info' parameter passed to FHTTP.ISSUE_REQUEST (consisting of tokens separated by unit separator characters [u001f]) does not contain the token that was expected at the specified index [1-relative].

Action:
Correct the 'authorization_info' parameter.

FRM-41713
error in FHTTP.ISSUE_REQUEST: invalid value {0} for token {1} [{2}] in "authorization_info"

Category:
Data

Cause:
The 'authorization_info' parameter passed to FHTTP.ISSUE_REQUEST (consisting of tokens separated by unit separator characters [u001f]) contains an invalid token at the specified index [1-relative]. In particular, token 1 [credential_id] must contain only alphanumeric characters and '_', '.', '-'.

Action:
Correct the 'authorization_info' parameter.

FRM-41714
error in FHTTP.ISSUE_REQUEST: logon dialog potentially required for an authorization that was not the last authorization in "authorization_info"

Category:
Data

Cause:
The 'authorization_info' parameter passed to FHTTP.ISSUE_REQUEST (consisting of tokens separated by unit separator characters [u001f]) contained multiple authorizations. One of them was of type Basic Authentication or OAuth2 Password. Such an authorization must be the last of the multiple authorizations.

Action:
Correct the 'authorization_info' parameter.

FRM-41715
error in FHTTP.ISSUE_REQUEST: username {0} specified for basic authentication in "authorization_info" contains a colon

Category:
Data

Cause:
The 'authorization_info' parameter passed to FHTTP.ISSUE_REQUEST (consisting of tokens separated by unit separator characters [u001f]) specified basic authentication as the authorization (or one of the authorizations). The username specified in token 3 [1-relative] contained a colon, which is not allowed for basic authentication.

Action:
Correct the 'authorization_info' parameter.

FRM-41721
error in FHTTP.ISSUE_REQUEST: authorization failed due to invalid config section name {0}

Category:
Data

Cause:
Authorization for HTTP requests to external services requires that the config section name specified as the config parameter in the frmservlet URL used to launch the Forms application contain only alphanumeric characters and '_', '.', '-'.

Action:
Specify a config section with a valid name in the frmservlet URL used to launch the Forms application.

FRM-41722
error in FHTTP.ISSUE_REQUEST: authorization failed due to missing credential for {0}

Category:
Configuration

Cause:
API Key and OAuth2 authorizations for HTTP requests to external services require that the Oracle Platform Security Services Credential Store contain a generic credential for the external service. The credential key must be of the form <config_section_name>=<credential_id>.

Action:
Use Fusion Middleware Control to add the generic credential. The value must be the key for API Key authorizations, and <client_id><LF><client_password> or <client_id><LF><client_secret> for OAuth2 authorizations. For OAuth2 Password authorizations, <LF><username><LF><password> may optionally be appended to the value. <LF> is the line-feed character [0x0a]. It may optionally be preceded by a carriage-return character [0x0d].

FRM-41723
error in FHTTP.ISSUE_REQUEST: authorization failed due to invalid credential for {0}

Category:
Configuration

Cause:
API Key and OAuth2 authorizations for HTTP requests to external services require that the Oracle Platform Security Services Credential Store contain a valid generic credential for the external service. A generic credential is allowed (but not required) for Basic Authentication authorizations. The credential key must be of the form <config_section_name>=<credential_id>. The value must be a string of the form <username>:<password> for basic authentication, and <client_id><LF><client_password> or <client_id><LF><client_secret> for OAuth2 authorization. For OAuth2 Password authorizations, <LF><username><LF><password> may optionally be appended to the value. <LF> is the line-feed character [0x0a]. It may optionally be preceded by a carriage-return character [0x0d].

Action:
Use Fusion Middleware Control to correct the generic credential.

FRM-41724
error in FHTTP.ISSUE_REQUEST: authorization failed due to rejected credential for {0}

Category:
Configuration

Cause:
The Oracle Platform Security Services Credential Store contained a generic credential value of the form <username>:<password> for a Basic Authentication authorization, or a generic credential value of the form <client_id><LF><client_password_or_secret><LF><username><LF><password> for an OAuth2 Password authorization, but the username and password were rejected by the external service.

Action:
Determine the correct username and password, and use Fusion Middleware Control to correct the generic credential.

FRM-41725
error in FHTTP.ISSUE_REQUEST: authorization failed due to invalid SSO user credential for {0}

Category:
Data

Cause:
In SSO mode, OAuth2 authorization information may be stored in a password credential for the SSO user in the Oracle Platform Security Services Credential Store, and reused for that user in subsequent Forms application sessions. However, when the stored information was subsequently retrieved, it was found to be in an incorrect format.

Action:
If the problem persists, contact Oracle Support Services. As a temporary workaround, you could use Fusion Middleware Control to remove the password credential, or you could disable SSO mode.

FRM-41760
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because the request to the token endpoint URL {1} encountered an error communicating with the token endpoint.

Category:
Network

Cause:
The request presented to the OAuth2 Token URL specified for OAuth2 authorization [as token 5 of the 'authorization_info' parameter] encountered an IOException while attempting to communicate with the token endpoint. A subsequent FRM-41692 message indicates where the stack trace for the IOException was written.

Action:
Inspect the stack trace in the response identified by message FRM-41692 in ODL. If the stack trace does not indicate how to fix the problem, and the problem persists, contact the owner of the external service.

FRM-41761
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because the request to the token endpoint URL {1} received unexpected response status code {2}. Details: {3}

Category:
Requests/Responses

Cause:
The request presented to the OAuth2 Token URL specified for OAuth2 authorization [as token 5 of the 'authorization_info' parameter] received a response status code other than 200. If the request specified a scope, [scope=<requested_permissions>] will appear in the error message immediately following the token endpoint URL.

Action:
Refer to the details that appear at the end of the message.

FRM-41762
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because the token endpoint URL {1} response {2} contained a syntax error or deviated from OAuth2 protocol at offset {3} [characters].

Category:
Requests/Responses

Cause:
The request presented to the OAuth2 Token URL specified for OAuth2 authorization [as token 5 of the 'authorization_info' parameter] received a response containing a violation of the syntax prescribed by RFC 8259 [JSON] and RFC 6749 [OAuth2].

Action:
Try to determine why the erroneous response is being returned, e.g. by contacting the owner of the external service.

FRM-41763
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because the token endpoint URL {1} response specified the unsupported token_type {2}.

Category:
Requests/Responses

Cause:
The request presented to the OAuth2 Token URL specified for OAuth2 authorization [as token 5 of the 'authorization_info' parameter] received a response that specified an unsupported token_type. Currently, only "bearer" is supported.

Action:
Redesign the Forms application.

FRM-41764
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because the request to the token endpoint URL {1} requested scope={2}, but the response granted only scope={3}.

Category:
Requests/Responses

Cause:
The request presented to the OAuth2 Token URL specified for OAuth2 authorization [as token 5 of the 'authorization_info' parameter] received a response that did not grant all requested permissions.

Action:
If the requested operation does not actually require all the requested permissions, remove the unneeded ones. Otherwise, contact the owner of the external service and/or redesign the Forms application.

FRM-41765
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because an Access Token Location of "Form Parameter" was specified, but request content-type was not "application/x-www-form-urlencoded".

Category:
Data

Cause:
The Access Token Location specified for OAuth2 authorization [as token 4 of the 'authorization_info' parameter] was 'Form Parameter', but the request content-type header was missing or specified a media type other than 'application/x-www-form-urlencoded'.

Action:
Correct the Access Token Location or the request content-type.

FRM-41766
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because the token endpoint URL {1} response did not specify an access token.

Category:
Requests/Responses

Cause:
The request presented to the OAuth2 Token URL specified for OAuth2 authorization [as token 5 of the 'authorization_info' parameter] received a response which did not contain an access token.

Action:
Try to determine why the erroneous response is being returned, e.g. by contacting the owner of the external service.

FRM-41769
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because the OAuth2 Token URL {1} was rejected.

Category:
Data

Cause:
The OAuth2 Token URL specified for OAuth2 authorization [as token 5 of the 'authorization_info' parameter] was malformed or did not specify a scheme of 'http', 'https', 'ws', or 'wss'.

Action:
Correct the OAuth2 Token URL.

FRM-41770
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because the attempt to redirect to the authorization endpoint URL {1} encountered an error.

Category:
Network

Cause:
A browser was launched to communicate with the OAuth2 authorization server at the OAuth2 Authorization URL specified for OAuth2 authorization [as token 7 of the 'authorization_info' parameter], but the attempt to redirect the browser response to that URL encountered an IOException. A subsequent FRM-41692 message indicates where the stack trace for the IOException was written.

Action:
Inspect the stack trace in the response identified by message FRM-41692 in ODL. If the stack trace does not indicate how to fix the problem, and the problem persists, contact the owner of the external service.

FRM-41771
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because the request to the authorization endpoint URL {1} produced an error. Details: {2}

Category:
Requests/Responses

Cause:
The request presented to the OAuth2 Authorization URL specified for OAuth2 authorization [as token 7 of the 'authorization_info' parameter] generated a response that indicated an error. If the request specified a scope, [scope=<requested_permissions>] will appear in the error message immediately following the authorization endpoint URL.

Action:
Refer to the details that appear at the end of the message.

FRM-41774
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because the request to the authorization endpoint URL {1} requested scope={2}, but only scope={3} was granted.

Category:
Requests/Responses

Cause:
A scope was specified in the request presented to the OAuth2 Authorization URL specified for OAuth2 authorization [as token 7 of the 'authorization_info' parameter], but the subsequent response from the token endpoint did not grant all requested permissions.

Action:
If the requested operation does not actually require all the requested permissions, remove the unneeded ones. Otherwise, contact the owner of the external service and/or redesign the Forms application.

FRM-41779
error in FHTTP.ISSUE_REQUEST: OAuth2 authorization failed for client {0} because the OAuth2 Authorization URL {1} was rejected.

Category:
Data

Cause:
The OAuth2 Authorization URL specified for OAuth2 authorization [as token 7 of the 'authorization_info' parameter] was malformed or did not specify a scheme of 'http', 'https', 'ws', or 'wss'.

Action:
Correct the OAuth2 Authorization URL.

FRM-41838
runtime process: unable to open temporary record buffer file

Category:
Files

Cause:
The runtime process was unable to open the file used as the temporary record buffer. A preceding FRM-91180 or FRM-91181 error message provides more detail. (FRM-91181 will occur if the error was on the first write attempt).

Action:
Refer to error message FRM-91180 and FRM-91181.

FRM-41839
runtime process: disk I/O error on temporary record buffer file

Category:
Files

Cause:
An I/O error occurred while the runtime process was attempting to read or write a record to the temporary record buffer file. A preceding FRM-91181 or FRM-91182 error message provides more detail.

Action:
Refer to error message FRM-91181 and FRM-91182.

FRM-60000
fatal error configuring Forms component

Category:
Configuration

Cause:
Forms component provisioning failed.

Action:
Examine the stack trace that accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60001
fatal error removing Forms component

Category:
Configuration

Cause:
Forms component deprovisioning failed.

Action:
Examine the stack trace that accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60002
error reading Forms component registration document {0}

Category:
Configuration

Cause:
An error occurred while reading the Forms component registration document.

Action:
Do one of the following: \n1. Make sure that the registration document is valid. \n2. If the registration document is accidentally deleted or modified then reinstall ORACLE_HOME.

FRM-60003
error reading ORACLE_HOME registry file {0}

Category:
Configuration

Cause:
An error occurred while reading the ORACLE_HOME registry file.

Action:
Do one of the following: \n1. Make sure that the ORACLE_HOME registry file exists. \n2. If ORACLE_HOME registry file is accidentally deleted or modified then reinstall ORACLE_HOME.

FRM-60004
error obtaining text contents of the configuration file {0}

Category:
Configuration

Cause:
Failed to read the text contents of the configuration file.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it.

FRM-60005
Directory {0} exists; renaming it to {1}

Category:
Configuration

Cause:
The subdirectory under the Oracle Instance directory already exists and the provisioning process renamed the existing subdirectory.

Action:
No action is required.

FRM-60006
error obtaining the managed server URL

Category:
Configuration

Cause:
Failed to obtain the managed server URL during Windows application deployment.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60007
error creating Windows shortcuts

Category:
Configuration

Cause:
Failed to create Windows shortcuts during configuration.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60008
error creating Forms instance {0}

Category:
Configuration

Cause:
Failed to create Forms instance.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60009
error updating Forms instance {0}

Category:
Configuration

Cause:
Failed to update Forms instance.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60010
error deleting Forms instance {0}

Category:
Configuration

Cause:
Failed to update Forms instance.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60011
error creating non-managed instance configuration

Category:
Configuration

Cause:
Failed to create Forms instance non-managed configuration.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60012
error updating/deleting instance: invalid Forms instance contents {0}

Category:
Configuration

Cause:
Failed to update Forms instance.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60013
error adding missing non-managed instance configuration

Category:
Configuration

Cause:
Failed to add missing Forms instance non-managed configuration.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60101
error registering Forms J2EE application MBeans during the application startup

Category:
Configuration

Cause:
An error occurred while registering the Forms J2EE application runtime MBean or custom configuration files MBeans.

Action:
Examine the stack trace that accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60102
error deregistering Forms J2EE application MBeans during the application shutdown

Category:
Configuration

Cause:
An error occurred while deregistering the Forms J2EE application runtime MBean or custom configuration files MBeans.

Action:
Examine the stack trace that accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60104
error reading the Forms System component instance

Category:
Configuration

Cause:
An error occurred while reading the Forms system component instance information.

Action:
Do one of the following:\n1. If there are multiple Forms system component instance on the same Weblogic machine, make sure that you have followed the steps in the Forms deployment guide.\n2. Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-60114
error reading default configuration path

Category:
Configuration

Cause:
An error occurred while obtaining the default configuration location.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-60201
error initializing identity store

Category:
Configuration

Cause:
An error occurred while reading the identity store configuration file.

Action:
Examine the stack trace that accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60202
Forms J2EE application {0} is already registered with Oracle Internet Directory host {1} under the container {2}. Deregistering it.

Category:
Configuration

Cause:
An attempt was made to re-create an existing Forms J2EE application footprint in Oracle Internet Directory. This may occur when the same Forms J2EE application is redeployed to the domain.

Action:
No action is required.

FRM-60203
error associating Forms application with Oracle Internet Directory host {0}

Category:
Configuration

Cause:
The Forms application footprint in Oracle Internet Directory failed to be created due to one of the following causes:\n 1. Oracle Internet Directory was not accessible.\n 2. The Forms J2EE application footprint password failed to be seeded in Oracle Platform Security Services on the mid-tier.\n 3. An I/O error occurred during storing of Oracle Internet Directory information from the Forms Oracle Internet Directory properties file.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60205
error disassociating Forms application with Oracle Internet Directory host {0}

Category:
Configuration

Cause:
Failed to remove the Forms J2EE application footprint from Oracle Internet Directory due to one of the following causes:\n 1. Oracle Internet Directory was not accessible.\n 2. An error status was returned while deregistering the Forms J2EE application footprint with Oracle Internet Directory.\n 3. Failed to fetch the Forms J2EE application footprint password from Oracle Platform Security Services on the mid-tier.\n 4. An I/O error occurred while cleaning Oracle Internet Directory information from the Forms Oracle Internet Directory properties file.

Action:
Do one of the following:\n 1. Examine the stack trace which accompanies this message, look for status of the IM tier and resolve the issue.\n 2. If using Fusion Middleware Control, make sure that information passed to deregister the Forms J2EE application with Oracle Internet Directory host is valid.\n 3. If the problem persists, contact Oracle Support Services.

FRM-60207
error storing credentials to Oracle Platform Security Services

Category:
Configuration

Cause:
An error occurred while storing the credentials to Oracle Platform Security Services.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60208
error deleting credentials from Oracle Platform Security Services

Category:
Configuration

Cause:
An error occurred while deleting the credentials from Oracle Platform Security Services.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60209
error obtaining credentials from Oracle Platform Security Services

Category:
Configuration

Cause:
An error occurred while reading the credentials from Oracle Platform Security Services.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60210
error obtaining MBean Server connection

Category:
Configuration

Cause:
An error occurred while connecting to the MBean Server.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60211
error migrating Resource Access Descriptor

Category:
Configuration

Cause:
An error occurred migrating Resource Access Descriptor to Oracle Platform Security Services.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60212
Resource Access Descriptor migration process interrupted

Category:
Configuration

Cause:
A running Resource Access Descriptor migration process was interrupted.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60213
error recording the Resource Access Descriptor migration result

Category:
Configuration

Cause:
An error occurred while recording the Resource Access Descriptor migration results.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60214
Forms Resource Access Descriptor migration thread awaken

Category:
Configuration

Cause:

Action:

FRM-60215
error reading the Resource Access Descriptor migration results

Category:
Configuration

Cause:
An error occurred while reading the Resource Access Descriptor migration results.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60216
error starting Forms Resource access migration to Oracle Platform Security Services

Category:
Configuration

Cause:
The Forms Resource Access Descriptor migration to Oracle Platform Security Services failed to start because the previous migration process is still running.

Action:
Wait for the exiting migration process to complete before running migration again.

FRM-60217
invalid Single Sign-on user

Category:
Configuration

Cause:
The user passed an invalid Single Sign-on user name to create a Resource Access Descriptor.

Action:
Provide a valid existing Single Sign-on user name and run the request again.

FRM-60218
error connecting to LDAP server

Category:
Configuration

Cause:
An error occurred while connecting the LDAP server due to one of the following causes: \n1. Invalid connection credentials were entered. \n2. Invalid hostname, port information was entered.\n3. LDAP server is down.

Action:
Examine the cause, and take the appropriate remedial action.

FRM-60220
error initializing the Forms Identity store

Category:
Configuration

Cause:
An error occurred while initializing the Forms Identity store.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60221
error obtaining the Forms identity store access

Category:
Configuration

Cause:
An error occurred while obtaining the Forms Identity store.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60222
error creating the FormsREST OPSS credential store map

Category:
Configuration

Cause:
An error occurred while creating FormsREST OPSS credential map.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60223
error accessing Forms local credential store

Category:
Configuration

Cause:
An error occurred while accessing Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60224
error writing to the Forms local credential store

Category:
Configuration

Cause:
An error occurred writing to the Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60225
error reading user from the Forms local credential store

Category:
Configuration

Cause:
An error occurred reading user from the Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60226
error decrypting credential in Forms local credential store

Category:
Configuration

Cause:
An error occurred decrypting credential in Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60227
error reading credential from the Forms local credential store

Category:
Configuration

Cause:
An error occurred reading credential from the Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60228
error reading credential comments from the Forms local credential store

Category:
Configuration

Cause:
An error occurred reading credential comments from the Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60229
error updating credential to the Forms local credential store

Category:
Configuration

Cause:
An error occurred updating credential to the Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60230
error storing credential to the Forms local credential store

Category:
Configuration

Cause:
An error occurred storing credential to the Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60231
error updating credential: invalid key {0} passed

Category:
Configuration

Cause:
An error occurred updating credential to the Forms local credential store because an invalid key passed.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60232
error updating credential: invalid map {0} passed

Category:
Configuration

Cause:
An error occurred updating credential to the Forms local credential store because an invalid map passed.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60233
error encrypting credential in Forms local credential store

Category:
Configuration

Cause:
An error occurred encrypting credential in Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60234
error initializing Forms local credential store

Category:
Configuration

Cause:
An error occurred initializing Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60235
error deleting credential from the Forms local credential store

Category:
Configuration

Cause:
An error occurred deleting credential from the Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60236
error deleting credential: invalid map {0} passed

Category:
Configuration

Cause:
An error occurred deleting credential to the Forms local credential store because an invalid map passed.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60237
error accessing RADs in the Forms local credential store

Category:
Configuration

Cause:
An error occurred accessing RADs in the Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60238
error deleting RADs in the Forms local credential store

Category:
Configuration

Cause:
An error occurred deleting RADs in the Forms local credential store.

Action
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60249
error creating Resource Access Descriptor for Forms application {0}: Resource Access Descriptor already exists

Category:
Configuration

Cause:
An error occurred while creating the Resource Access Descriptor because it already exists.

Action:
Edit the existing Resource Access Descriptor rather than adding it.

FRM-60250
error creating Resource Access Descriptor for Forms application {0}

Category:
Configuration

Cause:
An error occurred while creating the Resource Access Descriptor.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60251
error updating Resource Access Descriptor for Forms application {0}

Category:
Configuration

Cause:
An error occurred while updating the Resource Access Descriptor.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60252
error deleting Resource Access Descriptor for Forms application {0}

Category:
Configuration

Cause:
An error occurred while deleting the Resource Access Descriptor.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60253
error reading Resource Access Descriptor for Forms application {0}

Category:
Configuration

Cause:
An error occurred while reading the Resource Access Descriptor.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60254
error obtaining Resource Access Descriptor

Category:
Configuration

Cause:
An error occurred while obtaining the Resource Access Descriptor.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60255
error stashing Single Single-on user information in the Forms session

Category:
Configuration

Cause:
An error occurred while stashing Single Sign-on user information in the Forms session.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60256
permission error reading the Resource Access Descriptor from Oracle Internet Directory

Category:
Configuration

Cause:
Single Sign-on user does not have the right permission to read the Resource Access Descriptor.

Action:
No action is required.

FRM-60257
error reading Forms application {0}, Resource Access Descriptor for Single Sign-on User {1} from Oracle Internet Directory

Category:
Configuration

Cause:
An error occurred while obtaining the Forms application Resource Access Descritor from Oracle Internet Directory.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60258
error reading Forms application Resource Access Descriptor from Oracle Internet Directory

Category:
Configuration

Cause:
An error occurred while obtaining the Forms application Resource Access Descritor from Oracle Internet Directory.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60259
error processing line {0}: invalid syntax

Category:
Configuration

Cause:
An error occurred while processing the indicated line

Action:
Fix the entry and upload RADs again

FRM-60260
error processing line {0}: invalid set of parameters

Category:
Configuration

Cause:
An error occurred while processing the indicated entry

Action:
Fix the number of parameters at the indicated line

FRM-60261
error processing line {0}: invalid application name

Category:
Configuration

Cause:
An error occurred while processing the indicated entry

Action:
Add the missing application name and upload RADs again

FRM-60262
error processing line {0}: duplicate entry

Category:
Configuration

Cause:
An error occurred while processing the indicated entry

Action:
Delete the duplicate entry at the indicated line and upload RADs again

FRM-60263
error processing line {0}: missing Single Sign-on Username

Category:
Configuration

Cause:
An error occurred while processing the indicated entry

Action:
Add the Single Sign-on Username at the indicated line and upload RADs again

FRM-60264
error processing line {0}: invalid groupRad parameter value

Category:
Configuration

Cause:
An error occurred while processing the indicated entry

Action:
Fix the isGroupRad parameter value at the indicated line and upload RADs again

FRM-60265
error processing line {0}: missing dbUser parameter value

Category:
Configuration

Cause:
An error occurred while processing the indicated entry

Action:
Fix the dbUser parameter value at the indicated line and upload RADs again

FRM-60266
error processing line {0}: missing dbPassword parameter value

Category:
Configuration

Cause:
An error occurred while processing the indicated entry

Action:
Fix the dbPassword parameter value at the indicated line and upload RADs again

FRM-60301
invalid character in the file name argument {0}

Category:
Configuration

Cause:
An error occurred due to an invalid character in the file name.

Action:
Remove the invalid character from the file name and execute the operation again.

FRM-60302
error duplicating the configuration file {0} to {1}

Category:
Configuration

Cause:
An error occurred duplicating the configuration file due to one of the following causes: \n1. MBean registration failed. \n2. Failure to create a new file on the file system.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60303
error duplicating the configuration file {0}: invalid document type {1}

Category:
Configuration

Cause:
Invalid document type argument passed to operation.

Action:
Invoke the 'duplicate file' operation only on the supported valid document types (Type_default.env).

FRM-60304
error duplicating configuration file {0}: invalid argument {1} are passed to 'duplicate file' operation

Category:
Configuration

Cause:
The file the user tried to create already exists.

Action:
Pass a different file name for the new file that has to be created.

FRM-60305
error deleting the configuration file {0}

Category:
Configuration

Cause:
An error occurred deleting the configuration file due to one of the following causes: \n1. MBean deregistration failed. \n2. Failure to delete the file from the file system.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60306
error deleting the configuration file {0}: invalid document type {1}

Category:
Configuration

Cause:
An invalid document type argument was passed to the operation.

Action:
Invoke the 'duplicate file' operation only on the supported valid document types (Type_default.env).

FRM-60307
error converting the configuration object to the relevant CompositeType

Category:
Configuration

Cause:
Failed to convert the configuration object to the relevant CompositeType.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60308
error converting the configuration object to the relevant CompositeData

Category:
Configuration

Cause:
Failed to convert the configuration object to the relevant CompositeData.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it. If the problem persists, contact Oracle Support Services.

FRM-60309
error registering child config MBean for the application section {0}

Category:
Configuration

Cause:
Failed to register the child config MBean for the given application section.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it.

FRM-60310
error deregistering child config MBean for the application section {0}

Category:
Configuration

Cause:
Failed to deregister the child config MBean for the given application section.

Action:
Examine the stack trace which accompanies this message for the possible cause of failures and correct it.

FRM-60311
error deleting application section {0}

Category:
Configuration

Cause:
An attempt was made to delete the default application section or a section that does not exist.

Action:
Choose the correct section name.

FRM-60312
error creating application section {0}

Category:
Configuration

Cause:
An attempt was made to create an application section that already exists or has an invalid section name.

Action:
Choose an alternative name for the section.

FRM-60313
error duplicating application section {0} to {1}

Category:
Configuration

Cause:
Failed to duplicate an application section because of one of the following reasons:\n 1. An attempt was made to duplicate an invalid application section.\n 2. An attempt was made to create an application section that already exists.

Action:
Do one of the following:\n 1. Choose a correct section name for the duplicated application section.\n 2. Choose an alternative name for the newly created application section.

FRM-60314
error encrypting userid for forms application {0}

Category:
Configuration

Cause:
An unexpected error occurred while encrypting the userid parameter value.

Action:
If the problem persists, contact Oracle Support Services.

FRM-60315
error decrypting userid for forms application {0}

Category:
Configuration

Cause:
An unexpected error occurred while decrupting the the userid parameter value.

Action:
If the problem persists, contact Oracle Support Services.

FRM-60316
error encrypting forms userid

Category:
Configuration

Cause:
An unexpected error occurred while encrypting the userid parameter value.

Action:
If the problem persists, contact Oracle Support Services.

FRM-60317
error creating formsapp keystore

Category:
Configuration

Cause:
An unexpected error occurred while creating the formsapp keystore

Action:
If the problem persists, contact Oracle Support Services.

FRM-60318
error processing configuration, invalid entry at line:{0}

Category:
Configuration

Cause:
An unexpected error occurred while persisting the configuration.

Action:
Fix the configuration and submit it again.

FRM-91108
internal error in runtime process: unable to initialize PL/SQL

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to initialize PL/SQL.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91109
internal error in runtime process: application startup failure

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to start the Toolkit component.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91111
internal error in runtime process: window system startup failure

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to start the window system.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91112
internal error in runtime process: resource manager startup failure

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to start the Toolkit Resource Manager.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91116
internal error in runtime process: Oracle*Image startup failure

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to start Oracle*Image.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91119
internal error in runtime process: Oracle*VGS startup failure

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to start Oracle*VGS.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91124
fatal error in runtime process: {0} specified for FORMS_DECIMAL_PREFIX. Should be zero or the empty string

Category:
Configuration

Cause:
An invalid value was specified for the environment variable FORMS_DECIMAL_PREFIX.

Action:
Do one of the following: \n1. Specify FORMS_DECIMAL_PREFIX as '0' to force a zero before a leading decimal point in any number displayed without a format mask in the application. \n2. Specify FORMS_DECIMAL_PREFIX as '' (the empty string).

FRM-91126
fatal error in runtime process: invalid value {0} specified for environment variable {1}

Category:
Configuration

Cause:
An invalid environment variable value was specified. An example would be an invalid timezone for an environment variable that specifies a timezone.

Action:
Correct the environment variable value.

FRM-91127
runtime process: invalid directory name specified for environment variable {0}

Category:
Configuration

Cause:
An invalid value was specified for an environment variable that represents the name of a directory. Specifically, the value is too long: either it is itself longer than a system-imposed maximum, or a subdirectory name that Forms needs to construct would be longer than the system-imposed maximum. Execution of the runtime process might have been terminated, or it might have continued. In the latter case, the functionality that required this environment variable was disabled.

Action:
If this error message appears for DOMAIN_HOME or FORMS_INSTANCE_NAME, and the problem persists, contact Oracle Support Services. Otherwise, correct the environment variable value.

FRM-91128
runtime process warning: invalid value {0} specified for environment variable {1}; using default {2}

Category:
Configuration

Cause:
An invalid environment variable value was specified. The indicated default value was used, and processing continued.

Action:
Correct the environment variable value.

FRM-91129
runtime process: no value specified for required environment variable {0}

Category:
Configuration

Cause:
A required environment variable was not set or was set to the empty string. Execution of the runtime process might have been terminated, or it might have continued. In the latter case, the functionality that required this environment variable was disabled.

Action:
If this error message appears for DOMAIN_HOME or FORMS_INSTANCE_NAME, and the problem persists, contact Oracle Support Services. Otherwise, set the environment variable to a non-empty value.

FRM-91132
fatal error in runtime process: invalid data in timezone file {0}

Category:
Configuration

Cause:
The timezone file (specified by the environment variable FORMS_TZFILE) was found to contain invalid data.

Action:
Correct the FORMS_TZFILE environment variable value. It should specify $ORACLE_HOME/oracore/zoneinfo/timezone.dat or $ORACLE_HOME/oracore/zoneinfo/timezlrg.dat.

FRM-91134
fatal error in runtime process: NLS_LANG specifies unsupported character set

Category:
Configuration

Cause:
The NLS_LANG environment variable specified a character set which is not ASCII-based, e.g. fixed-width Unicode or an EBCDIC-based character set.

Action:
Correct the NLS_LANG environment variable value.

FRM-91135
fatal error in runtime process: message file {0} is missing

Category:
Configuration

Cause:
The specified message file was not found.

Action:
Verify that the file has not been moved or deleted. If necessary, reinstall it.

FRM-91137
runtime process: unable to open log file {0}

Category:
Configuration

Cause:
An invalid name was specified for a log file or a trace file. The name might be too long, or it might specify a non-existent or read-only directory. In the former case, the error message

shows the name truncated at the maximum allowable length, followed by 3 dots. Execution of the runtime process might have been terminated, or it might have continued. In the latter case, messages that subsequently would have been written to the file were silently discarded.

Action:
Correct the environment variable used to specify the directory (e.g. FORMS_TRACE_DIR), and/or the file name proper (which might have been specified e.g. by the value of the 'log' configuration parameter). If no environment variable or configuration parameter was set to specify the directory or the file name proper, and the problem persists, contact Oracle Support Services.

FRM-91138
runtime process: unable to create log file {0}

Category:
Configuration

Cause:
An attempt to open, write, or close a log file failed.

Action:
Verify that the directory specified for the log file has appropriate write privileges and adequate disk space.

FRM-91143
internal error in runtime process: unable to create runform global context

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to create the runform global context.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91144
internal error in runtime process: unable to parse user name

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to parse the user name.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91145
fatal error in runtime process: missing serverArgs parameter

Category:
Configuration

Cause:
If this error occurred when using the Forms Servlet, both the serverArgs configuration parameter and the serverArgs applet parameter (either of which can represent the command-line arguments that are passed to the frmweb executable) were either missing or had a blank value. If this error occurred for static HTML (HTML that's not generated by the Forms Servlet), the serverArgs applet parameter was either missing or had a blank value.

Action:
If this error occurred for static HTML, add a serverArgs parameter to the applet. Otherwise, ensure that the Forms Servlet configuration file or the base HTML files correctly define a serverArgs parameter. [Note that the base HTML files that are shipped with the produce omit the serverArgs parameter, but the shipped Forms Servlet configuration file specifies a non-blank value.]

FRM-91150
internal error in runtime process: unable to initialize Oracore program manager

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to initialize the Oracore program manager.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91151
internal error in runtime process: unable to initialize Oracle NLS

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to initialize Oracle NLS.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91152
internal error in runtime process: unable to set environment variable {0}

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to set an environment variable to a new value.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91153
internal error in runtime process: unable to initialize Common Area component

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to initialize the Common Area component.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91154
internal error in runtime process: unable to initialize Oracore date component

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to initialize the Oracore date component.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91157
internal error in runtime process: unable to redirect stderr to stdout

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to redirect stderr to stdout. This error should never occur at a customer site.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91160
BI Publisher integration error: {0}

Category:
Configuration

Cause:
The runtime process attempted to communicate with BI Publisher but an exception occurred. Some more information about the specific exception is included in this message, which may help to resolve the problem.

Action:
Attempt to use the information provided to resolve the problem. If the problem persists, contact Oracle Support Services.

FRM-91170
runtime process: JVM exiting with code {0}

Category:
Process

Cause:
The runtime process had started a JVM (in order to run Oracle Reports or the Forms debugger, or to update a password in Oracle Internet Directory). That JVM started exiting.

Action:
No action is required.

FRM-91171
runtime process: JVM aborting

Category:
Process

Cause:
The runtime process had started a JVM (in order to run Oracle Reports or the Forms debugger, or to update a password in Oracle Internet Directory). That JVM started aborting.

Action:
No action is required. However, if there appear to be problems running Oracle Reports or the Forms debugger, or updating a password in Oracle Internet Directory, this message may help to indicate the cause.

FRM-91180
fatal error in runtime process: error {0} ({1}) attempting to open temporary record buffer file

Category:
Files

Cause:
An attempt to open the temporary record buffer file encountered the indicated error. Both the error number (errno on Unix and GetLastError() on Windows) and the corresponding error string are given. The runtime process was terminated.

Action:
Examine the error string, and take appropriate remedial action. Verify that the file system or directory in which the file resides exists and that the runtime process has permissions to read and write to the file system or directory.

FRM-91181
runtime process: error {0} ({1}) attempting to write {2} bytes to offset {3} of temporary record buffer file {4}

Category:
Files

Cause:
The specified 'write' operation to the temporary record buffer file encountered the indicated error. Both the error number (errno on Unix and GetLastError() on Windows) and the corresponding error string are given. Execution continued, for the moment at least; however, an error other than "out of space" is likely to cause subsequent termination of the runtime process (message FRM-91195).

Action:
Examine the error string, and take appropriate remedial action. Verify that the file system or directory in which the file resides exists, and that the runtime process has permissions to read and write to the file system or directory, and that the file system contains sufficient space.

FRM-91182
runtime process: error {0} ({1}) attempting to read {2} bytes from offset {3} of temporary record buffer file {4}

Category:
Files

Cause:
The specified 'read' operation to the temporary record buffer file encountered the indicated error. Both the error number (errno on Unix and GetLastError() on Windows) and the corresponding error string are given. Execution continued, for the moment at least; however, the error is likely to cause subsequent termination of the runtime process (message FRM-91195).

Action:
Examine the error string, and take appropriate remedial action.

FRM-91183
runtime process: error {0} ({1}) attempting to allocate {2} bytes at offset {3} of temporary record buffer file {4}

Category:
Files

Cause:
The specified 'allocate' operation ('fallocate' on Linux and 'posix_fallocate' on other Unix platforms) to the temporary record buffer file encountered the indicated error. Both the error number (errno) and the corresponding error string are given. Execution continued, for the moment at least; however, an error other than "out of space" is likely to cause subsequent termination of the runtime process (message FRM-91195).

Action:
Examine the error string, and take appropriate remedial action. Verify that the file system or directory in which the file resides exists, and that the runtime process has permissions to read and write to the file system or directory, and that the file system contains sufficient space.

FRM-91184
runtime process: error {0} ({1}) attempting to truncate or extend temporary record buffer file {2} to {3} bytes

Category:
Files

Cause:
The specified 'ftruncate' operation to the temporary record buffer file encountered the indicated error. Both the error number (errno) and the corresponding error string are given. Execution continued, for the moment at least; however, an error other than "out of space" is likely to cause subsequent termination of the runtime process (message FRM-91195).

Action:
Examine the error string, and take appropriate remedial action. Verify that the file system or directory in which the file resides exists, and that the runtime process has permissions to read and write to the file system or directory, and that the file system contains sufficient space.

FRM-91185
runtime process: error {0} ({1}) attempting to close temporary record buffer file {2}

Category:
Files

Cause:
An attempt to close the temporary record buffer file encountered the indicated error. Both the error number (errno on Unix and GetLastError() on Windows) and the corresponding error string are given. Execution continued; however, it's possible that the temporary record buffer file was not deleted properly.

Action:
Examine the error string, and take appropriate remedial action.

FRM-91190
fatal error in runtime process: unable to allocate {0} bytes of memory

Category:
Memory

Cause:
A critical memory allocation request failed. This may indicate insufficient swap space. Execution of the runtime process was terminated.

Action:
Increase the size of the swap space, or rerun the application when the system is less heavily loaded.

FRM-91191
runtime process: unable to allocate {0} bytes of memory; attempting to continue execution

Category:
Memory

Cause:
A memory allocation request failed. This may indicate insufficient swap space. Execution continued, but the current operation (e.g. the loading of a form) failed. And a subsequent critical memory allocation may have failed, thereby terminating the runtime process.

Action:
Increase the size of the swap space, or rerun the application when the system is less heavily loaded.

FRM-91192
fatal error in runtime process: unable to memory-map {0} bytes of memory

Category:
Memory

Cause:
A memory-map request failed. This probably indicates insufficient swap space. Execution of the runtime process was terminated.

Action:
Increase the size of the swap space, or rerun the application when the system is less heavily loaded.

FRM-91193
runtime process: unable to memory-map {0} bytes of memory; attempting to continue execution

Category:
Memory

Cause:
A memory-map request failed. This probably indicates insufficient swap space. Execution continued, but the current operation (e.g. the loading of a form) failed. And a subsequent critical memory allocation may have failed, thereby terminating the runtime process.

Action:
Increase the size of the swap space, or rerun the application when the system is less heavily loaded.

FRM-91194
fatal error in runtime process: unable to allocate memory for critical record manager operation

Category:
Memory

Cause:
A memory allocation failure (reported in a preceding FRM-91191 message) occurred while attempting a record manager operation, and the operation was subsequently deemed critical. Execution of the runtime process was terminated.

Action:
Increase the size of the swap space, or rerun the application when the system is less heavily loaded.

FRM-91195
fatal error in runtime process: cannot recover from disk I/O error on temporary record buffer file

Category:
Files

Cause:
A disk I/O error on the temporary record buffer file (reported in a preceding FRM-41839 message and in a FRM-91181 or FRM-91182 message preceding that) caused a critical operation to fail. Execution of the runtime process was terminated. Note that an "out of space" error on a write is *not* fatal.

Action:
Examine the preceding FRM-91181 or FRM-91182 message.

FRM-91196
fatal error in runtime process: unable to memory-map {0} bytes of memory backed by a file

Category:
Memory

Cause:
A memory-map request backed by a file failed. This probably indicates insufficient space in the file system (e.g. /tmp). Execution of the runtime process was terminated.

Action:
Increase the size of the file system, or rerun the application when the system is less heavily loaded.

FRM-91197
runtime process: unable to memory-map {0} bytes of memory backed by a file; attempting to continue execution

Category:
Memory

Cause:
A memory-map request backed by a file failed. This probably indicates insufficient space in the file system (e.g. /tmp). Execution continued, but the current operation (e.g. the loading of a form) failed. And a subsequent critical memory allocation may have failed, thereby terminating the runtime process.

Action:
Increase the size of the file system, or rerun the application when the system is less heavily loaded.

FRM-91199
internal error in runtime process: assertion failure: file {0}, line {1}

Category:
Process

Cause:
An assertion failed in code that the runtime process was executing.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91200
fatal error in runtime process: error reading HTTP header

Category:
Network

Cause:
A fatal error occurred while attempting to read an HTTP header.

Action:
Check for problems on the network that connects the Forms Java Client with the Forms Listener Servlet and the runtime process.

FRM-91210
fatal error in runtime process: error reading HTTP data

Category:
Network

Cause:
A fatal error occurred while attempting to read HTTP data.

Action:
Check for problems on the network that connects the Forms Java Client with the Forms Listener Servlet and the runtime process.

FRM-91220
fatal error in runtime process: error writing HTTP data

Category:
Network

Cause:
A fatal error occurred while attempting to write HTTP data.

Action:
Check for problems on the network that connects the Forms Java Client with the Forms Listener Servlet and the runtime process.

FRM-91230
fatal error in runtime process: timeout on connection to Java client

Category:
Network

Cause:
The runtime process was waiting for a message from the Java client, but none appeared within the timeout interval. (This interval defaults to 15 minutes, but can be overridden by the FORMS_TIMEOUT environment variable.)

Action:
Check for problems on the network that connects the Forms Java Client with the Forms Listener Servlet and the runtime process. Also check to see if the Forms applet on the Java client experienced a fatal error.

FRM-91260
internal error in runtime process: unable to initialize the Winsock DLL

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to initialize the Winsock DLL.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91270
runtime process unable to allocate socket for protocol {0}: {1}

Category:
Process

Cause:
The runtime process was unable to allocate a socket for the indicated protocol (IPv4 or IPv6). The error message from the operating system is displayed.\n NOTE: If this error was detected for an IPv4 socket, the runtime process continued execution (and subsequently attempted to configure an IPv6 socket). If this error was detected for an IPv6 socket and an IPv4 socket was not successfully configured, then the runtime process was terminated.

Action:
If the error message from the operating system indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-91272
runtime process unable to set close-on-exec on socket for protocol {0}: {1}

Category:
Process

Cause:
The runtime process was unable to configure the socket that it allocated for the indicated protocol (IPv4 or IPv6), to set close-on-exec. The error message from the operating system is displayed. The runtime process attempted to continue execution.

Action:
If the error message from the operating system indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-91273
runtime process unable to enable local address reuse on socket for protocol {0}: {1}

Category:
Process

Cause:
The runtime process was unable to configure the socket that it allocated for the indicated protocol (IPv4 or IPv6), to enable local address reuse. The error message from the operating system is displayed.\n NOTE: If this error was detected for an IPv4 socket, the runtime process continued execution (and subsequently attempted to configure an IPv6 socket). If this error was detected for an IPv6 socket and an IPv4 socket was not successfully configured, then the runtime process was terminated.

Action:
If the error message from the operating system indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-91274
runtime process unable to translate hostname ({0}) to an address for protocol {1}: {2}

Category:
Process

Cause:
The runtime process was unable to configure the socket that it allocated for the indicated protocol (IPv4 or IPv6) correctly, because the hostname could not be translated to an address. The error message from the operating system is displayed.\n NOTE: If this error was detected for an IPv4 socket, the runtime process continued execution (and subsequently attempted to configure an IPv6 socket). If this error was detected for an IPv6 socket and an IPv4 socket was not successfully configured, then the runtime process was terminated.

Action:
If the error message from the operating system indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-91275
runtime process unable to bind socket address for port {0} to socket for protocol {1}: {2}

Category:
Process

Cause:
The runtime process was unable to configure the socket that it allocated for the indicated protocol (IPv4 or IPv6), to bind the socket address for the indicated port to it. The error message from the operating system is displayed.\n NOTE: If this error was detected for an IPv4 socket, the runtime process continued execution (and subsequently attempted to

configure an IPv6 socket). If this error was detected for an IPv6 socket and an IPv4 socket was not successfully configured, then the runtime process was terminated.

Action:
If the error message from the operating system indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-91276
runtime process unable to obtain port number of socket for protocol {0}: {1}

Category:
Process

Cause:
The runtime process was unable to obtain the port number of the socket that it allocated for the indicated protocol (IPv4 or IPv6). The error message from the operating system is displayed. This error should never occur at a customer site.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91277
internal error in runtime process: unable to write port and process ID information to stderr

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to write port and process ID information to standard error. This error should never occur at a customer site.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91278
runtime process unable to listen for connections on socket for protocol {0}: {1}

Category:
Process

Cause:
The runtime process was unable to configure the socket that it allocated for the indicated protocol (IPv4 or IPv6), to listen for connections. The error message from the operating system is displayed.\n NOTE: If this error was detected for an IPv4 socket, the runtime process continued execution (and subsequently attempted to configure an IPv6 socket). If this error was detected for an IPv6 socket and an IPv4 socket was not successfully configured, then the runtime process was terminated.

Action:
If the error message from the operating system indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-91279
runtime process unable to restrict IPv6 socket to IPv6 only: {0}

Category:
Process

Cause:
The runtime process was unable to configure the socket that it allocated for IPv6, to restrict its use to IPv6 only (as opposed both IPv6 and IPv4). The error message from the operating system is displayed. The runtime process attempted to continue execution, but a subsequent attempt to bind the socket might fail with the error "address already in use".

Action:
If the error message from the operating system indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-91280
runtime process unable to set non-blocking I/O on socket for protocol {0}: {1}

Category:
Process

Cause:
The runtime process was unable to set non-blocking I/O on the socket that it allocated for the indicated protocol (IPv4 or IPv6). The error message from the operating system is displayed. The runtime process attempted to continue execution.

Action:
If the error message from the operating system indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-91292
internal error in runtime process: invalid initial message from Java client

Category:
Process

Cause:
The initial message from the Java client to the runtime process was not in the expected format.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91293
internal error in runtime process: invalid initial message from servlet

Category:
Process

Cause:
The initial message from the servlet to the runtime process was not in the expected format.

Action:
If the problem persists, contact Oracle Support Services.

FRM-91299
fatal error in runtime process: unable to create a connection to the Java client

Category:
Process

Cause:
An unexpected error occurred while the runtime process was attempting to create a connection to the Java client. Usually, a previous message provides more detail.

Action:
If a previous error message indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-91930
message from Forms application: {0}

Category:
Other

Cause:
The Forms application called the MESSAGE built-in with an option of ODL_DEBUG.

Action:
Respond as directed by the application developer.

FRM-91934
message from Forms application: {0}

Category:
Other

Cause:
The Forms application called the MESSAGE built-in with an option of ODL_NOTIFICATION.

Action:
Respond as directed by the application developer.

FRM-91935
message from Forms application: {0}

Category:
Other

Cause:
The Forms application called the MESSAGE built-in with an option of ODL_WARNING.

Action:
Respond as directed by the application developer.

FRM-91936
message from Forms application: {0}

Category:
Other

Cause:
The Forms application called the MESSAGE built-in with an option of ODL_ERROR.

Action:
Respond as directed by the application developer.

FRM-91940
module {0} loaded by Forms runtime process

Category:
Other

Cause:
The Forms application caused the specified module to be opened.

Action:
No action is required.

FRM-91990
runtime process: A maximum of {0}K bytes were simultaneously allocated for archived record data.

Category:
Performance

Cause:
The runtime process allocated the indicated amount of memory without reserving swap space or /tmp file space. The memory will be included in many reports of memory usage (such as the output of the Linux pmap command), but it will not consume system resources (real memory or disk) until it is actually used for archived record data. (See FRM-91992).

Action:
No action is required.

FRM-91991
runtime process: A maximum of {0}K bytes were simultaneously allocated and reserved for archived record data.

Category:
Performance

Cause:
The runtime process allocated the indicated amount of memory, and reserved swap space or /tmp file space for it.

Action:
No action is required. However, if the number reported by this message is significantly larger than the number reported by FRM-91992 and you are using mapped-memory archiving (FORMS_RECMGR_ARCHIVE unset, or set to MAP_SWAP or MAP_TMPFILE), you may want to reduce the value of FORMS_RECMGR_BLOCK_SIZE (which defaults to 64K when memory is being reserved, but can be set as low as 32K). Better yet, don't reserve memory that's allocated for archived record data, if possible. (This can be accomplished in most Unix installations, by setting FORMS_RECMGR_RESERVE_SPACE to '0').

FRM-91992
runtime process: A maximum of {0}K bytes were simultaneously in use for archived record data.

Category:
Performance

Cause:
The runtime process used the indicated amount of memory for archived record data. Specifically, at time of maximum usage, it (the runtime process) had written data into the pages of memory, and the data was still needed at that point (because there was a possibility that the record might subsequently need to be activated). Note that when

FORMS_RECMGR_ARCHIVE has been set to WRITE_TMPFILE, the runtime process has no way of notifying the file system when it no longer needs a page, and so the file system may retain an unneeded page in a real-memory buffer for a while. Thus, in this case the number reported by this message should be viewed as lower bound.

Action:
No action is required. However, the numbers reported by this message for various applications may help to determine an appropriate value for FORMS_RECMGR_ARCHIVE_THRESHOLD.

FRM-91994
runtime process: When total memory in use for archived record data was at its maximum, record groups required {0}K bytes for archived record data, plus approximately {1}K additional bytes for active record data and record anchors. If FORMS_RECMGR_USED_FOR_RECGRPS were set to FALSE, a total of approximately {2}K bytes would instead have been required.

Category:
Performance

Cause:
At the point in time when total memory in use for archived record data was at its maximum (as reported by FRM-91992), the runtime process used the sum of the first two amounts for all data and anchors for all records in record groups, but would instead have used the third amount if FORMS_RECMGR_USED_FOR_RECGRPS had been set to FALSE.

Action:
No action is required. However, the numbers reported by this message for various applications may help to determine the appropriate value for FORMS_RECMGR_USED_FOR_RECGRPS. [Bear in mind that TRUE (the default) requires more CPU than FALSE.]

FRM-91995
runtime process: The record manager is currently consuming the following for {0}: {1}

Category:
Performance

Cause:
The Forms application issued a call to the GET_RECMGR_STATS built-in, which then issued this message. The parameter {1} in this message is a formatted report of the amount of various types of memory currently being consumed for record data of the type indicated by the parameter {0} in this message (which corresponds to the argument passed to GET_RECMGR_STATS: all_record_data, archived_record_data, active_record_data, or record_anchors). The formatted report lists Kbytes of memory for the following 6 types of memory: MALLOCED, MAPPED, MAPPED_IN_USE, MAPPED_RESERVED, WRITTEN, WRITTEN_IN_USE.

Action:
No action is required.

FRM-93100
Initializing the Forms Servlet. Initialization parameters are:{0}

Category:
Configuration

Cause:
The Forms Servlet was being initialized.

Action:
No action is required.

FRM-93110
No Forms Servlet configuration file is specified.

Category:
Configuration

Cause:
The configFileName initialization parameter was not specified.

Action:
Specify the full name in the servlet parameter configFileName, the system property oracle.forms.configFileName, or the servlet context parameter configFileName.

FRM-93111
Cannot find Forms Servlet configuration file {0}.

Category:
Configuration

Cause:
The Forms Servlet configuration file (specified by the configFileName initialization parameter) was not found.

Action:
Verify that the configFileName initialization parameter specifies the correct value. (The value is taken from the servlet parameter configFileName, the system property oracle.forms.configFileName, or the servlet context parameter configFileName.) Create the file if necessary.

FRM-93112
error reading Forms Servlet configuration file {0}

Category:
Files

Cause:
An I/O error occurred while reading the specified file.

Action:
If the error persists, determine if the file has been damaged. Re-create the file if necessary.

FRM-93113
syntax error at line {0} in configuration file {1}: invalid section name "{2}"

Category:
Configuration

Cause:
The specified configuration file contained an invalid section name.

Action:
Provide a valid section name.

FRM-93114
Forms Servlet configuration file {0} contains invalid data.

Category:
Configuration

Cause:
A syntax error was detected while parsing the specified file.

Action:
A preceding FRM-93113 or FRM-93142 error message will provide more information. Take the action indicated for the FRM-93113 or FRM-93142 message.

FRM-93115
error reading ORACLE_HOME registry file

Category:
Configuration

Cause:
An error occurred while reading the ORACLE_HOME registry file.

Action:
Do one of the following:\n1. Make sure that the ORACLE_HOME registry file exists.\n2. If ORACLE_HOME registry file is accidentally deleted or modified then reinstall ORACLE_HOME.

FRM-93121
Cannot find environment variable configuration file {0}.

Category:
Configuration

Cause:
One of the following occurred. (The first is by far the most likely.) Note that an envFile parameter may specify a relative path; if it was not found in the current directory, Forms will search for it in the directory that contains the Forms Servlet configuration file. \n1. The envFile configuration parameter for this application specified a nonexistent file. A preceding FRM-93141 error message provides details. \n2. The envFile configuration parameter for this application specified a file that existed when the Forms Servlet extracted the parameter, but the file subsequently disappeared. \n3. No envFile configuration parameter that would apply to this application was specified, and the envFile servlet parameter specified a nonexistent file.

Action:
Take action depending on the cause. \n1. Take action indicated for the preceding FRM-93141 error message. \n2. Re-create the file, or correct the envFile configuration parameter. \n3. Verify that the envFile servlet parameter specifies the correct value. Create the file if necessary.

FRM-93122
error reading environment variable configuration file {0}

Category:
Files

Cause:
An I/O error occurred while reading the specified file.

Action:
If the error persists, determine if the file has been damaged. Re-create the file if necessary.

FRM-93124
Environment variable configuration file {0} contains invalid data.

Category:
Configuration

Cause:
The specified configuration file contained an invalid section name.

Action:
Provide a valid section name.

FRM-93128
invalid value {0} specified for environment variable FORMS_HTTP_PROXY_PORT or FORMS_HTTPS_PROXY_PORT; proxy host ignored.

Category:
Configuration

Cause:
This error is typically detected when attempting to access an external service (e.g. a REST service). An invalid environment variable value (non-numeric, < 0, or > 65535) was specified for FORMS_HTTP_PROXY_PORT or FORMS_HTTPS_PROXY_PORT. The value that was specified for FORMS_HTTP_PROXY_HOST or FORMS_HTTPS_PROXY_HOST was ignored, and processing continued. However, in the absence of a proxy, the attempt to access the external service may fail.

Action:
Correct the environment variable value.

FRM-93130
No base HTML file is specified.

Category:
Configuration

Cause:
Java Web Start was not enabled, but the basehtml configuration parameter was not specified, nor was the basehtmljpi configuration parameter, where relevant. (See Oracle Fusion Middleware Forms Services Deployment Guide for details about which configuration parameter is appropriate.) The FRM-93140 error message provides details about which configuration sections were searched. (Note that the error message will always refer to the basehtml configuration parameter, not the basehtmljpi configuration parameter.)

Action:
Specify the appropriate configuration parameter.

FRM-93131
Cannot find base HTML file {0}.

Category:
Configuration

Cause:
Java Web Start was not enabled, but the specified base HTML file was not found. This file is typically specified by the basehtml configuration parameter, but in certain cases may be specified by the basehtmljpi configuration parameter. The FRM-93141 error message provides

details. Note that the parameter may specify a relative path; if the file is not found in the current directory, Forms will search for the file in the directory that contains the Forms Servlet configuration file.

Action:
Verify that the parameter specifies the correct file. Create the file if necessary.

FRM-93132
error reading base HTML or JNLP file {0}

Category:
Files

Cause:
An I/O error occurred while reading the specified file.

Action:
If the error persists, determine if the file has been damaged. Re-create the file if necessary.

FRM-93134
No base JNLP file is specified.

Category:
Configuration

Cause:
Java Web Start was enabled or a JNLP file was embedded in the HTML file, but the basejnlp configuration parameter was not specified. The FRM-93140 error message provides details about which configuration sections were searched.

Action:
Specify the basejnlp configuration parameter.

FRM-93135
Cannot find base JNLP file {0}.

Category:
Configuration

Cause:
Java Web Start was enabled or a JNLP file was embedded in the HTML file, but the specified base JNLP file was not found. This file is specified by the basejnlp configuration parameter. The FRM-93141 error message provides details. Note that the parameter may specify a relative path; if the file is not found in the current directory, Forms will search for the file in the directory that contains the Forms Servlet configuration file.

Action:
Verify that the basejnlp parameter specifies the correct file. Create the file if necessary.

FRM-93136
no base TXT file specified for Oracle Forms Standalone Application

Category:
Configuration

Cause:
The baseSAAfile configuration parameter was not specified.

Action:
Specify the baseSAAfile configuration parameter.

FRM-93140
Section [{0}] of Forms Servlet configuration file {1} does not specify (or inherit) a value for the required parameter {2}.

Category:
Configuration

Cause:
A required configuration parameter was not specified in the indicated configuration section or in a parent section.

Action:
Specify the parameter value in the indicated section, or in a parent section. (See Oracle Fusion Middleware Forms Services Deployment Guide for details about what values are expected.)

FRM-93141
Section [{0}] of Forms Servlet configuration file {1} specifies the nonexistent file {2} for parameter {3}.

Category:
Configuration

Cause:
A configuration parameter in the indicated configuration section specified the name of a nonexistent file.

Action:
Verify that the parameter specifies the correct file. Create the file if necessary.

FRM-93142
Section [{0}] of Forms Servlet configuration file {1} specifies the invalid value "{2}" for parameter {3}.

Category:
Configuration

Cause:
An invalid configuration parameter value was specified in the indicated configuration section. Note that invalid values for certain crucial parameters (such as HTMLdelimiter) will cause a subsequent error, FRM-93114.

Action:
Correct the parameter value. (See Oracle Fusion Middleware Forms Services Deployment Guide for details about what values are expected.)

FRM-93143
Oracle Forms Standalone Launcher checksum failed.

Category:
Configuration

Cause:
The checksum received from the client did not match the Oracle Forms Standalone Launcher jar.

Action:
Contact your system administrator or get the latest Oracle Forms Standalone Launcher file.

FRM-93144
error while generating checksum of Oracle Forms Standalone Launcher file

Category:
Configuration

Cause:
An I/O error occurred while generating the checksum.

Action:
Check if Oracle Forms Standalone Launcher file exists.

FRM-93153
New connections to this Forms Servlet are not being allowed. Attempting to redirect connection attempt to {0}.

Category:
Configuration

Cause:
The allowNewConnections configuration parameter was false, and a value was specified for the connectionDisallowedURL configuration parameter. Redirection will be attempted to that URL.

Action:
No action is required.

FRM-93154
The Forms Servlet is not allowing new connections.

Category:
Configuration

Cause:
The allowNewConnections configuration parameter was false, and either no value was specified for the connectionDisallowedURL configuration parameter, or else redirection to the specified URL failed.

Action:
If a value is specified for the connectionDisallowedURL configuration parameter (as indicated in error message FRM-93153), check to see if the specified URL is malformed; if so, correct the URL. Otherwise, no action is required.

FRM-93156
The Forms Servlet is unable to contact the Forms Load Balancing Server at {0}:{1}.

Category:
Configuration

Cause:
The Forms Servlet was unable to contact the indicated Forms Load Balancing Server, and the MetricsServerErrorURL configuration parameter was not specified.

Action:
Do one or both of the following. \n1. Determine why the server is unavailable, and correct the condition. \n2. Specify a value for the MetricsServerErrorURL parameter in the Forms Servlet configuration file.

FRM-93160
unexpected error while obtaining the JVM pid

Category:
Process

Cause:
An Exception was encountered while obtaining the JVM process ID.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93162
unexpected error loading native library {0}

Category:
Process

Cause:
An Exception was encountered while loading native library.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93176
Command "{0}" is using default ORACLE_HOME setting: {1}.

Category:
Configuration

Cause:
A test command has retrieved the specified value for the ORACLE_HOME environment variable, from the environment variable configuration file specified by the envFile parameter in the default section of the Forms Servlet configuration file.

Action:
No action is required.

FRM-93180
Initializing ListenerServlet. Initialization parameters are: {0}

Category:
Configuration

Cause:
The Forms Listener Servlet was being initialized.

Action:
No action is required.

FRM-93196
Process list file {0} does not exist or is not writable; process list disabled.

Category:
Configuration

Cause:
When a runtime process was started or stopped, an attempt was made to write an updated list of runtime processes to the specified file, but it did not exist or was not writable. Note that the name of the process list file is obtained from the em_process_file parameter in the URL, the Forms Servlet configuration file, or the environment variable configuration file.

Action:
Verify that the em_process_file parameter specifies the correct file. If necessary, create the file or make it writable, or both.

FRM-93197
unexpected error while obtaining the application name from JRF

Category:
Configuration

Cause:
An Exception was encountered while obtaining the application name from JRF.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93198
unexpected error while obtaining the cluster name from JRF

Category:
Configuration

Cause:
An Exception was encountered while obtaining the cluster name from JRF.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93211
error decoding query string using {0} encoding. Spaces generated from "+" in the value of otherparams may be converted to "%20".

Category:
Configuration

Cause:
There was a mismatch between the way that the browser encoded multibyte characters and the way that the Forms Servlet decoded them. This could indicate an invalid value for the defaultcharset parameter in the configuration file, or possibly a problem in either the browser or Oracle software.

Action:
If the site uses the otherparams parameter in any URLs, verify that the defaultcharset parameter in the configuration file is correct; if the defaultcharset parameter is correct, contact Oracle Support Services. Otherwise, no action is required.

FRM-93214
internal buffer ({0} bytes) not big enough to read request content ({1} bytes)

Category:
Requests/Responses

Cause:
An internal buffer was not big enough to read the content of a request from the Java client. The FRM-93214 error message provides supplemental detail for the FRM-93218 error message.

Action:
If the problem persists, contact Oracle Support Services.

FRM-93217
unable to read whole request from client: expected {0}, got {1}

Category:
Requests/Responses

Cause:
A fatal error occurred while reading the content of a request from the Java client. The FRM-93217 error message provides supplemental detail for the FRM-93218 error message.

Action:
Check for problems on the network that connects the Forms Java Client with the Forms Listener Servlet.

FRM-93218
fatal error reading client request content

Category:
Requests/Responses

Cause:
A fatal error occurred while attempting to read the content of a request from the Java client. A preceding FRM-93214 or FRM-93217 error message might provide more detail.

Action:
Check for problems on the network that connects the Forms Java Client with the Forms Listener Servlet.

FRM-93226
fatal error redirecting response to {0}

Category
Requests/Responses

Cause:
A fatal error occurred while redirecting a response. A subsequent FRM-93227 will display the stack trace

Action:
Check for problems on the network that connects the Forms Java Client with the Forms Listener Servlet.

FRM-93227
stack trace for preceding FRM-93226:

Category
Requests/Responses

Cause:
This message displays the stack trace associated with the preceding FRM-93226 message.

Action:
Check for problems on the network that connects the Forms Java Client with the Forms Listener Servlet.

FRM-93228
fatal error writing response to client

Category:
Requests/Responses

Cause:
A fatal error occurred while writing a response to the Forms Java client.

Action:
Check for problems on the network that connects the Forms Java Client with the Forms Listener Servlet.

FRM-93240
Multiple Forms applications cannot share an HTTP session.

Category:
Session

Cause:
A Forms application was launched in such a way that it attempted to share an HTTP session with an already running Forms application. This might result from one of the following:\n1. The user selected File, then New, then Browser Window (or Ctrl+N) in Internet Explorer while the servlet session was being tracked using cookies (that is, session cookies were enabled). In this case Forms does not support creating a new session for the second window.\n2. An application attempted to launch multiple Forms applications, and session cookies were enabled in the Forms application.\n3. An application attempted to launch multiple Forms applications using POST, cookies were disabled in the Forms application, and the launching application specified the same cookie name as did the Forms application.

Action:
Take action depending on the cause.\n1. No action is required.\n2. Disable session cookies in the Forms application.\n3. Change the cookie name in the launching application or the Forms application. This can be accomplished via <cookie-name> under <session-descriptor> in the weblogic.xml deployment descriptor.

FRM-93245
HTTP session not found on target server; possible load balancer configuration issue.

Category:
Session

Cause:
A GET request to the Forms Servlet or Forms Listener Servlet that was not for SSO Web Start specified a session ID (e.g. jsessionid) in a cookie or the URL, but no matching HTTP session was found on the server machine to which the request was directed. This might result from one of the following:\n1. A load balancer was not correctly configured to support sticky sessions.\n2. (1) cookies were disabled in weblogic.xml, (2) an intermediate agent timed out while an Oracle Forms Standalone application was waiting for an end user to do SSO login or to submit a Resource Access Descriptor (RAD) during SSO authentication, and (3) the preserveHttpSessionId configuration parameter was not set to true.

Action:
Take action depending on the cause.\n1. Verify that the load balancer is correctly configured to support session stickiness.\n2. Try reducing the value specified for the ssoSaaWaitInterval configuration parameter. [It defaults to 25 seconds.] Note that setting the preserveHttpSessionId configuration parameter to true will produce the more illuminating FRM-93248 in this case [i.e. when conditions (1) and (2) are true].

FRM-93248
connection to the server apparently closed after a request had executed for {0,number,#0.000} seconds, probably due to an intermediate agent timing out

Category:
Configuration

Cause:
This message may appear in the terminal window from which a Standalone application was launched. The Oracle Forms Standalone Launcher was waiting for SSO authentication to complete. When the wait exceeds the interval specified by the ssoSaaWaitInterval configuration parameter, the original request returns and the Standalone Launcher issues a new request, repeating until SSO authentication is complete. However, it appears that one of those requests failed, probably due to a timeout in an intermediate agent, which in turn caused the connection to the server to be closed.

Action:
Reduce the value specified for the ssoSaaWaitInterval configuration parameter. [It defaults to 25 seconds.]

FRM-93249
launch of browser window to be used for SSO authentication of an Oracle Forms Standalone application timed out after {0} seconds

Category:
Configuration

Cause:
This message will appear in the terminal window from which the Standalone application was launched. One of the following occurred:\n1. The browser was not launched at all, probably because java.awt.Desktop is not supported on the current platform. This message will be preceded by an FRM-92493 error message.\n2. The browser was launched, but the request generated by its initial URL did not specify a valid HTTP session, probably because a load balancer did not direct the request to the correct server. An FRM-93245 error message will appear on the launched browser window.\n3. A slow network or an overloaded client machine prevented the browser launch from completing within the indicated time interval (specified by

the ssoSaaBrowserLaunchTimeout configuration parameter). The time interval is measured from the initial invocation of frmsal.jar that launched the application.

Action:
Take action depending on the cause.\n1. Launch the Standalone application on a platform which supports java.awt.Desktop.\n2. Verify that the load balancer is correctly configured to support session stickiness.\n3. Increase the value specified by ssoSaaBrowserLaunchTimeout configuration parameter.

FRM-93250
Forms session started.

Category:
Session

Cause:
This message was generated on the initial request from the browser to the Forms Servlet, before an HTTP session was created.

Action:
No action is required.

FRM-93251
Runtime session started for client {0} (IP address {1}).

Category:
Session

Cause:
This message was generated when the runtime process was created (typically just after the HTTP session was created). If performance monitoring was requested, it started at this point.

Action:
No action is required.

FRM-93252
Forms session ended.

Category:
Session

Cause:
This message was generated when the runtime process was terminated. If performance monitoring was requested, it stopped at this point.

Action:
No action is required.

FRM-93301
Fatal authentication error: Unable to connect to Oracle Internet Directory.

Category:
Security

Cause:
A NamingException occurred while attempting to connect to Oracle Internet Directory.

Action:
Verify that the Oracle Internet Directory is up.

FRM-93302
error running Forms in SSO mode.

Category:
Security

Cause:
The OHS instance front-ending Forms managed server is not configured to run with Webgate.

Action:
Configure OHS with the Webgate access client. Refer to the Forms documentation.

FRM-93304
No resource information found for key {0}.

Category:
Security

Cause:
No resource information was found for the specified key in Oracle Internet Directory. This message might be followed by error message FRM-93330 or FRM-93318.

Action:
If a subsequent error message appears, take the action indicated for that error. Otherwise, no action is required.

FRM-93306
Encountered {0} while attempting to retrieve database credentials from Oracle Internet Directory.

Category:
Security

Cause:
A UtilException was encountered while attempting to retrieve database credentials from Oracle Internet Directory. This message might be followed by error message FRM-93330, FRM-93316, or FRM-93318.

Action:
If a subsequent error message appears, take the action indicated for that error. Otherwise, no action is required.

FRM-93308
Unable to get the User Distinguished Name (DN) for the User or the Subscriber

Category:
Security

Cause:
An Exception occurred while attempting to get the User Distinguished Name for the Oracle Access Manager user from Oracle Internet Directory

Action:
Verify that the Oracle Internet Directory is Up.

FRM-93310
Encountered {0} while attempting to decode headers from mod_osso.

Category:
Security

Cause:
An Exception was encountered while attempting to decode headers from mod_osso.

Action:
If a subsequent error message appears, take the action indicated for that error. Otherwise, no action is required.

FRM-93316
Encountered {0} while attempting to obtain user credentials. Redirecting to Delegated Administration Services.

Category:
Security

Cause:
A NoPermissionException occurred while attempting to obtain credentials. The user will be redirected to Delegated Administration Services.

Action:
If a subsequent error message appears, take the action indicated for that error. Otherwise, no action is required.

FRM-93318
Encountered {0} while attempting to obtain user credentials. Redirecting to Delegated Administration Services or to the SSO error URL.

Category:
Security

Cause:
A NamingException that is not a NoPermissionException occurred while attempting to obtain user credentials.

Action:
If a subsequent error message appears, take the action indicated for that error. Otherwise, no action is required.

FRM-93320
unable to obtain application entity credential from Oracle Platform Security Services

Category:
Security

Cause:
The Forms servlet could not retrieve application credential from Oracle Platform Security Services to connect to OID. One of the following was true: \n1. The Forms application did not have privileges to connect to Oracle Platform Security Services. \n2. Oracle Platform Security Services alias and key values were invalid.

Action:
Check whether credentials exist and are valid.

FRM-93322
unable to obtain user credentials; redirecting to Resource Access Descriptor servlet

Category:
Security

Cause:
User credentials were not obtained, and either the symptom was a NoPermissionException, or the ssoDynamicResourceCreate configuration parameter was true.

Action:
No action is required.

FRM-93324
Encountered {0} while attempting to obtain the Delegated Administration Services URL.

Category:
Security

Cause:
A UtilException was encountered while attempting to obtain the Delegated Administration Services URL.

Action:
Verify that Delegated Administration Services is up.

FRM-93326
Delegated Administration Services URL generated: {0}

Category:
Security

Cause:
The Forms application was running in SSO mode, the user did not have proper credentials configured in Oracle Internet Directory, and redirection to Delegated Administration Services was requested. This message provides the URL for Delegated Administration Services.

Action:
No action is required.

FRM-93328
User credentials not obtained; redirecting to the SSO error URL.

Category:
Security

Cause:
User credentials were not obtained. The error was not due to a NoPermissionException. The ssoDynamicResourceCreate configuration parameter was not true. If the ssoErrorURL configuration parameter was not defined, this message will be followed by error message FRM-93140, which will provide details.

Action:
No action is required.

FRM-93330
Fatal authentication error: User does not have proper credentials configured.

Category:
Security

Cause:
The user did not have proper credentials configured in the Identity Store (Oracle Internet Directory or Oracle Platform Security Services), and one of the following was true: \n1. The ssoDynamicResourceCreate configuration parameter was true, or the user did not have the necessary permissions to access Oracle Internet Directory.\n2. The ssoDynamicResourceCreate configuration parameter was not true and the ssoErrorURL configuration parameter was not defined.

Action:
Add the user credentials to the Identity Store (Oracle Internet Directory or Oracle Platform Security Services), if appropriate. Alternatively, define the ssoErrorURL configuration parameter.

FRM-93331
Fatal authentication error: Invalid Single Sign-On User.

Category:
Security

Cause:
There was a failure to obtain the Single Sign-On user information after authentication.

Action:
Re-login using SSO credentials. If the problem persists, contact Oracle Support Services.

FRM-93340
Session requires SSO user authentication.

Category:
Security

Cause:
The session was not SSO-authenticated or had expired.

Action:
No action is required.

FRM-93350
failure in SSO user validation

Category:
Security

Cause:
The Forms Listener Servlet decoded a request's SSO headers, but the values did not match the values from the Forms Servlet. The user was prompted to log in again.

Action:
No action is required.

FRM-93360
This session is in SSO mode.

Category:
Security

Cause:
The ssoMode parameter was specified as true in the base configuration file, and the servlet supported authentication.

Action:
No action is required.

FRM-93362
unable to update password in Oracle Internet Directory

Category:
Security

Cause:
The user did not have proper credentials configured in Oracle Internet Directory to update entries.

Action:
Check with the Oracle Internet Directory administrator to see if the user has permissions to update entries in Oracle Internet Directory.

FRM-93364
Cannot dynamically create resource in Oracle Internet Directory: URL specifies invalid value "{0}" for the config parameter.

Category:
Security

Cause:
The Forms application was running in SSO mode, the user did not have proper credentials configured in Oracle Internet Directory, and SSO dynamic resource creation was enabled. However, dynamic resource creation requires a valid configuration section in the base configuration file, but the user specified a nonexistent configuration section.

Action:
No action is required.

FRM-93365
error running Forms in SSO mode

Category:
Files

Cause:
Forms is not configured to run in SSO mode.

Action:
Configure Forms to run in SSO mode.

FRM-93366
error creating Forms application's Resource Access Descriptor in Oracle Internet Directory.

Category:
Security

Cause:
The Forms application failed to dynamically create a Resource Access Descriptor (RAD) in Oracle Internet Directory.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93367
invalid parameters {0} passed to the Forms Rad Servlet

Category:
Security

Cause:
Invalid parameters were passed to the Forms Rad Servlet.

Action:
If the problem persists, contact Oracle Support Services.

FRM-93368
Forms Rad Servlet is in an invalid state.

Category:
Security

Cause:
Invalid Http session detected in the Forms Rad Servlet. This should never happen.

Action:
If the problem persists, contact Oracle Support Services.

FRM-93369
Direct user access of Forms RadServlet is not allowed.

Category:
Security

Cause:
User tried to access the Forms RadServlet directly.

Action:
No action is required.

FRM-93370
error reading the Resouce Access Descriptor for update

Category:
Security

Cause:
Forms Rad Servlet failed to read the Resouce Access Descriptor to update it due to an internal error.

Action:
If the problem persists, contact Oracle Support Services.

FRM-93371
error closing connection with Oracle Internet Directory

Category:
Security

Cause:
Forms encountered an error closing connection with Oracle Internet Directory.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93380
unexpected error while attempting to redirect to Oracle Access Manager or the Forms Rad servlet

Category:
Security

Cause:
An IOException or ServletException was encountered while attempting to do a sendRedirect or forward to Oracle Access Manager or the Forms Rad servlet.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93382
Oracle Access Manager login processing for an Oracle Forms Standalone application timed out after {0} seconds

Category:
Configuration

Cause:
This message will appear in the terminal window from which the Standalone application was launched. The user did not complete Oracle Access Manager login within the indicated time interval (specified by the ssoSaaBrowserPageTimeout configuration parameter). The time interval is measured from when the page was displayed.

Action:
Increase the time interval specified by ssoSaaBrowserPageTimeout configuration parameter if it is deemed inadequate.

FRM-93383
Resource Access Descriptor processing for an Oracle Forms Standalone application timed out after {0} seconds

Category:
Configuration

Cause:
This message will appear in the terminal window from which the Standalone application was launched. The user did not press Submit or Cancel in the Resource Access Descriptor page within the indicated time interval (specified by the ssoSaaBrowserPageTimeout configuration parameter). The time interval is measured from when the page was displayed.

Action:
Increase the time interval specified by ssoSaaBrowserPageTimeout configuration parameter if it is deemed inadequate.

FRM-93410
unexpected error while prestarting runtime processes

Category:
Process

Cause:
An unchecked Exception or Error was encountered while prestarting runtime processes. The prestarting of runtime processes might not have occurred at all, or it might have been partially completed.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93412
There are {0} prestarted runtime processes in the runtime process pool for configuration section [{1}].

Category:
Process

Cause:
During runtime process pool initialization, the indicated number of runtime processes were prestarted for the indicated configuration section, because the configuration section specified a value of true for the prestartRuntimes parameter. (The number of runtime processes is derived from the prestartInit parameter.)

Action:
No action is required.

FRM-93421
starting the timer for the runtime process pool for configuration section [{0}]

Category:
Process

Cause:
During runtime process pool initialization, a timer task was started for the indicated configuration section, because the configuration section specified a positive value for the prestartTimeOut parameter.

Action:
No action is required.

FRM-93423
adding {0} runtime processes to the runtime process pool for configuration section [{1}] because the pool has gone below the minimum

Category:
Process

Cause:
A prestarted runtime process was removed from the runtime process pool for the indicated configuration section, in order to start a new Forms application. This caused the number of prestarted runtime processes to fall below the value specified by the prestartMin parameter.

As a result, the indicated number of prestarted runtime processes (derived from the prestartIncrement parameter) were added to the pool.

Action:
No action is required.

FRM-93424
removing the prestarted runtime processes for configuration section [{0}]

Category:
Process

Cause:
The servlet was being shut down, or the prestarting of runtime processes timed out (as indicated by message FRM-93425). As a result, prestarted processes were removed from the pool.

Action:
No action is required.

FRM-93425
The prestarting of runtime processes for configuration section [{0}] has timed out.

Category:
Process

Cause:
The thread that was filling the runtime process pool for the indicated configuration section timed out, after running for the number of minutes specified by the prestartTimeOut parameter for the indicated configuration section. Any prestarted processes in the pool were subsequently removed.

Action:
Determine why prestarting was taking an unexpectedly long time, or increase the value of the prestartTimeOut parameter.

FRM-93426
The prestarting of runtime processes for configuration section [{0}] is terminated.

Category:
Process

Cause:
A concurrent process removed the indicated configuration section's entry in the PoolManager while its runtime process pool was being filled. Any prestarted processes in the pool were subsequently removed.

Action:
No action is required.

FRM-93430
scheduling prestart event: {0}.

Category:
Process

Cause:
A scheduled prestart timer event was processed, resulting in the prestart of one or more Forms runtime processes.

Action:
No action is required.

FRM-93431
unexpected error while prestarting Forms runtime processes for the pre-start event: {0}

Category:
Process

Cause:
An Exception was encountered while prestarting Forms runtime processes for a scheduled prestart event.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93432
error adding notification listener to the Timer MBean

Category:
Process

Cause:
An Exception was encountered while adding notification listener to the Timer MBean.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93433
schedules restored from prestart archive file

Category:
Process

Cause:
Notifications were added to the prestart Timer MBean from the prestart archive file.

Action:
No action is required

FRM-93434
error restoring schedule {0} from the prestart archive file

Category:
Process

Cause:
An Exception was encountered while restoring a schedule from the prestart archive file.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93435
error restoring schedules from the prestart archive file

Category:
Process

Cause:
An Exception was encountered while restoring the schedules from the prestart archive file.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93436
schedules are written to the prestart archive file

Category:
Process

Cause:
Schedules from the prestart Timer MBean were dumped to the prestart archive file before the Forms application was shutdown.

Action:
No action is required

FRM-93437
error writing schedules to the prestart archive file

Category:
Process

Cause:
An Exception was encountered while writing schedules to the prestart archive file.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93438
error prestarting Forms runtime processes for the event: {0}

Category:
Process

Cause:
The scheduled Forms runtime processes could not be prestarted because of an invalid entry in the notification event from the prestart Timer MBean.

Action:
No action is required.

FRM-93439
scheduled prestart event not processed for configuration section [{0}]

Category:
Process

Cause:
The prestart scheduling event was not processed because the prestartRuntimes parameter is not set in formsweb.cfg.

Action:
Enable the prestartRuntimes parameter in formsweb.cfg.

FRM-93500
unexpected error while attempting to create the runtime process

Category:
Process

Cause:
An unchecked Exception or Error was encountered while attempting to create the runtime process. Typically, a runtime process creation error would cause a more specific message.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93520
Runtime process not created: Maximum permissible number of runtime processes is exceeded.

Category:
Configuration

Cause:
The maxRuntimeProcesses configuration parameter specified a positive decimal number, and there appeared to be that many runtime processes already executing.

Action:
No action is required.

FRM-93530
unable to switch to working directory {0}

Category:
Configuration

Cause:
The specified file did not exist or was not a directory. Note that the name of the working directory is obtained from one of the following: \n1. The workingDirectory parameter in the Forms Servlet configuration file. \n2. The workingDirectory servlet parameter. \n3. <oracle_home>/forms, where <oracle_home> is derived from the ORACLE_HOME parameter in the environment variable configuration file. \n4. <oracle_home>/forms, where <oracle_home> is derived from the ORACLE_HOME environment variable.

Action:
For cases 1 and 2, verify that the workingDirectory parameter specifies the correct directory. For cases 3 and 4, verify that the ORACLE_HOME parameter or environment variable specifies the correct directory. If necessary, create the directory.

FRM-93531
cannot create runtime process: unable to switch to working directory

Category:
Configuration

Cause:
Refer to error message FRM-93530 (which always precedes this message). The FRM-93530 message provides the name of the directory.

Action:
Refer to error message FRM-93530.

FRM-93534
unable to execute startup command {0}

Category:
Process

Cause:
The specified command (which was intended to start the runtime process) threw an Exception. The command was retried with <oracle_home>/bin prefixed, but that too threw an Exception. A stack trace accompanies the following FRM-93535 error message. This error should never occur at a customer site. Note that <oracle_home> is derived from one of the following:\n1. The ORACLE_HOME parameter in the environment variable configuration file.\n2. The ORACLE_HOME environment variable.

Action:
Contact Oracle Support Services.

FRM-93535
cannot create runtime process: unable to execute startup command

Category:
Process

Cause:
Refer to error message FRM-93534 (which always precedes this message). The FRM-93534 error message specifies the command. This error should never occur at a customer site.

Action:
Contact Oracle Support Services.

FRM-93536
cannot create runtime process: unable to create temporary logging file

Category:
Files

Cause:
An IOException occurred while trying to create a temporary logging file to capture the standard output and standard error streams of the newly created runtime process.

Action:
Verify that the Forms Listener Servlet has the necessary permissions and disk space to create a temporary file.

FRM-93543
cannot connect to runtime process: unable to get I/O streams from newly created runtime process

Category:
Process

Cause:
The Forms Listener Servlet encountered an Exception when attempting to obtain a BufferedInputStream for the standard output or standard error streams produced by the newly created runtime process. This error should never occur at a customer site.

Action:
Contact Oracle Support Services.

FRM-93546
external message from runtime process: {0}

Category:
Process

Cause:
The runtime process wrote the specified message to stderr or stdout, but the message does not appear to have been written by the frmweb exeutable. It typically will be an O/S message identifying an error that occurred while attempting to load the executable. In such a case, this message will be followed immediately by FRM-93552.

Action:
Examine the external message. If it identifies a fatal error, correct it, if possible. If the problem persists, contact Oracle Support Services.

FRM-93548
Runtime process ID is {0}.

Category:
Process

Cause:
The newly created runtime process sent its process ID back to the Forms Listener Servlet.

Action:
No action is required.

FRM-93550
cannot connect to runtime process: no response from newly created runtime process

Category:
Process

Cause:
The Forms Listener Servlet waited several times (for a total of roughly 4 minutes) for the initial response from the newly created runtime process, but no response arrived.

Action:
If the problem persists, contact Oracle Support Services.

FRM-93552
cannot connect to runtime process: Newly created runtime process has terminated abnormally.

Category:
Process

Cause:
The Forms Listener Servlet created the runtime process, but the process terminated abnormally. The preceding error message provides more detail.

Action:
Take the action indicated for the preceding error message.

FRM-93553
cannot connect to runtime process: unable to establish a socket connection to newly created runtime process

Category:
Process

Cause:
The Forms Listener Servlet created the runtime process, but was unable to establish a socket connection to the process.

Action:
If the problem persists, contact Oracle Support Services.

FRM-93558
cannot connect to runtime process: error reading data from newly created runtime process

Category:
Process

Cause:
The Forms Listener Servlet encountered an IOException while attempting to receive data from the newly created runtime process.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93566
unexpected error while attempting to stop runtime process

Category:
Process

Cause:
An unchecked Exception or Error was encountered while attempting to stop the runtime process. Processing continued. However, the runtime process might have been left in existence (thereby consuming resources), and messages from the runtime process might not have been written to the Oracle Diagnostic Log.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93572
error reading messages from runtime process

Category:
Files

Cause:
An I/O error occurred while reading the temporary file to which messages from the runtime process were written. Processing continued. However, messages from the runtime process were not written to the Oracle Diagnostic Log.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93574
Application server does not support Oracle character set {0}.

Category:
Configuration

Cause:
The runtime process used the specified Oracle character set when it wrote messages for the Oracle Diagnostic Log, but the application server did not support that character set. Processing continued, using the ISO-8859-1 Java character set. However, some multibyte characters (those in variable arguments) in messages from the runtime process might have been displayed incorrectly in the Oracle Diagnostic Log.

Action:
Verify that the environment variable configuration file specifies the correct value for NLS_LANG (specifically, the correct character set). If the problem persists, contact Oracle Support Services.

FRM-93600
unexpected error while attempting to communicate with the client or the runtime process

Category:
Process

Cause:
An unchecked Exception or Error was encountered while attempting to communicate with the client or the runtime process. Typically, a communication error would cause a more specific message.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93614
invalid or absent Content-Length from runtime process

Category:
Process

Cause:
This message provides more detail for the following FRM-93618 error message.

Action:
Refer to error message FRM-93618.

FRM-93618
fatal error reading data from runtime process

Category:
Process

Cause:
The runtime process was still running, but the Forms Listener Servlet encountered an IOException while attempting to receive data from the process. A preceding message might provide more detail. The accompanying stack trace represents the state of the process when the previous detail message was logged.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93624
internal buffer ({0} bytes) not big enough to hold header ({1} bytes) for message from servlet to runtime process

Category:
Requests/Responses

Cause:
An internal buffer was not big enough to hold the header for a message from the servlet to the runtime process. The FRM-93624 error message provides supplemental detail for the FRM-93628 error message.

Action:
If the problem persists, contact Oracle Support Services.

FRM-93625
internal buffer ({0} bytes) not big enough to generate initial message from servlet to runtime process

Category:
Requests/Responses

Cause:
An internal buffer was not big enough to generate the initial message from the servlet to the runtime process. The FRM-93625 error message provides supplemental detail for the FRM-93628 error message.

Action:
If the problem persists, contact Oracle Support Services.

FRM-93628
fatal error writing data to runtime process

Category:
Process

Cause:
The runtime process was still running, but the Forms Listener Servlet encountered a fatal error while attempting to write data to the process. A preceding FRM-93624 or FRM-93625 error message might provide more detail.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93652
The runtime process has terminated abnormally.

Category:
Process

Cause:
The Forms Listener Servlet attempted to communicate with the runtime process, but the process had terminated prematurely. The preceding error message provides more detail.

Action:
Take the action indicated for the preceding error message.

FRM-93654
Runtime process {0} is terminating due to external action.

Category:
Process

Cause:
The runtime process was running on a UNIX platform, and received a signal 9 (SIGKILL) or 15 (SIGTERM), or the runtime process was running on a Windows platform, and exited with exit code 1. Presumably the runtime process was terminated explicitly, either via the Enterprise Manager, or via a 'kill' command (UNIX) or the task manager (Windows). As a result, the runtime process terminated abnormally. This message provides more detail for a following FRM-93552 or FRM-93652 error message.

Action:
No action is required.

FRM-93656
Runtime process {0} is terminating due to signal {1}.

Category:
Process

Cause:
The runtime process was running on a UNIX platform, and received a signal other than 9 (SIGKILL) or 15 (SIGTERM). The signal caused the runtime process to terminate abnormally. This message provides more detail for a following FRM-93552 or FRM-93652 error message. If the FORMS_CATCHTERM environment variable was not set to a value that is equivalent to FALSE, there will typically be a stack trace. If the FORMS_C_STACK_TRACE_TO_FILE environment variable was set to a value that is equivalent to FALSE, the stack trace will accompany this message; otherwise, the stack trace will appear in a file named frmweb_dump_<pid> in the Forms trace directory, where <pid> is the process ID. If the FORMS_CATCHTERM environment variable was set to a value that is equivalent to FALSE, there may be a core file that contains a stack trace.

Action:
Examine the stack trace for the runtime process. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93657
Runtime process {0} is terminating due to exception {1}.

Category:
Process

Cause:
The runtime process was running on a Windows platform, and encountered an exception (which is displayed as 8 hexadecimal digits in the error message, in some cases followed by a descriptive phrase). The exception caused the runtime process to terminate abnormally. This message provides more detail for a following FRM-93552 or FRM-93652 error message. If the FORMS_CATCHTERM environment variable was not set to a value that is equivalent to FALSE, there will typically be a stack trace. If the FORMS_C_STACK_TRACE_TO_FILE environment variable was set to a value that is equivalent to FALSE, the stack trace will accompany this message; otherwise, the stack trace will appear in a file named frmweb_dump_<pid> in the Forms trace directory, where <pid> is the process ID.

Action:
Examine the stack trace for the runtime process. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93658
Stack trace for runtime process {0} is being written to file {1}.

Category:
Process

Cause:
The runtime process encountered a signal or an exception (identified by the preceding "FRM-93656" or "FRM-93657" message), and the FORMS_C_STACK_TRACE_TO_FILE environment variable was not set to a value that is equivalent to FALSE.

Action:
No action is required.

FRM-93659
Stack trace for runtime process {0} cannot be written to file {1}.

Category:
Process

Cause:
The runtime process encountered a signal or an exception (identified by the preceding "FRM-93656" or "FRM-93657" message), and the FORMS_C_STACK_TRACE_TO_FILE environment variable was not set to a value that is equivalent to FALSE. However, the stack trace file could not be created.

Action:
Ensure that the FORMS_TRACE_DIR environment variable (if set) and the ORACLE_INSTANCE environment variable each specify a valid directory with write permissions and adequate space.

FRM-93660
unable to get the hostname, using localhost instead of hostname in the Forms DMS table

Category:
Process

Cause:
The runtime process was unable to read the hostname from the server.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93661
error writing JVM Controller pid file

Category:
Process

Cause:
The runtime process was unable to write the JVM Controller pid file to the disk.

Action:
Ensure that ORACLE_INSTANCE/FRComponent/frcommon/tools/jvm/proc directory exists, the user running Weblogic server has write permissions to write to it and there is adequate disk space.

FRM-93662
error initializing OPMN metrics collection

Category:
Process

Cause:
The runtime process was unable to initialize OPMN metrics collection.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93700
Request duration is {0} seconds. Request size is {1} bytes; response size is {2} bytes.

Category:
Performance

Cause:
Performance monitoring at the request level was requested.

Action:
No action is required.

FRM-93710
Total duration of network exchanges is {0}. Total number of network exchanges is {1} ({2} long ones over {3} sec). Average time for one network exchange (excluding long ones) is {4}. Total number of bytes sent is {5}. Total number of bytes received is {6}.

Category:
Performance

Cause:
Performance monitoring at the session level was requested.

Action:
No action is required.

FRM-93840
Proctest: Warning: nProcs configuration parameter is nonnumeric - using 1.

Category:
Configuration

Cause:
A nonnumeric value was specifed for the nProcs parameter in the base configuration file. The value will default to 1.

Action:
Correct the nProcs configuration parameter.

FRM-93841
Proctest: Process test starting with {0} processes.

Category:
Process

Cause:
The Proctest command started.

Action:
No action is required.

FRM-93842
Proctest: Creating process {0}.

Category:
Process

Cause:
The Proctest command started creating a runtime process.

Action:
No action is required.

FRM-93843
Proctest: Failure to create process {0} - aborting test.

Category:
Process

Cause:
An Exception occurred while attempting to create a runtime process. The preceding error message identifies the problem, and includes a stack trace.

Action:
Refer to the preceding error message.

FRM-93844
Proctest: Connecting to process {0}.

Category:
Process

Cause:
The Proctest command started connecting to a newly created runtime process.

Action:
No action is required.

FRM-93845
Proctest: Failure to connect to process {0} - aborting test.

Category:
Process

Cause:
An Exception occurred while attempting to connect to a newly created runtime process. The preceding error message identifies the problem, and includes a stack trace.

Action:
Refer to the preceding error message.

FRM-93846
Proctest: unexpected error in process test

Category:
Process

Cause:
This message precedes error message FRM-93843 or FRM-93845 if the problem was an Error or an unchecked Exception that was not caught by Forms code. A stack trace is included.

Action:
Examine the stack trace that accompanies this message. If the stack trace indicates a possible cause, correct it. If the problem persists, contact Oracle Support Services.

FRM-93847
Proctest: Number of processes started and connected to is {0}.

Category:
Process

Cause:
The Proctest command created the requested number of runtime processes, and successfully connected to them.

Action:
No action is required.

FRM-93848
Proctest: Stopping the {0} runtime processes.

Category:
Process

Cause:
The Proctest command reached the point in its processing where it was about to stop the runtime processes that it had previously created.

Action:
No action is required.

FRM-93849
Proctest: Process test complete.

Category:
Process

Cause:
The Proctest command completed.

Action:
No action is required.

FRM-93893
Trace: Xlate encountered an IO error

Category:
Files

Cause:
The Xlate utility encountered an IOException.

Action:
Examine the stack trace.

FRM-94170
File {0} is missing from the current directory, looking in {1}.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94171
File is missing from {0}.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94172
Environment variable configuration file is {0}.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94173
Value of serverArgs generated from configuration file and URL is "{0}".

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94178
Enterprise Manager configuration details: {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94200
FormsServlet receiving {0} request. Details: {1}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94201
ListenerServlet receiving {0} request. Details: {1}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94202
HTTP request headers: {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94212
Unable to get the Sequence Number from Pragma Header (Mac Client). Obtaining the seqNumber from the Accept header instead.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94213
forwarding 0 length request to runtime in response to request to close Forms session

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94231
starting new servlet session with ID {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94232
FormsServlet: encodeURL() has no effect.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94233
Server URL is rewritten. Details:{0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94241
ListenerServlet: encodeURL() has no effect.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94253
servlet session with ID {0} is invalidated.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94254
HTTP session ID changed to {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94282
Existing servlet session, ID = {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94283
No current servlet session.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94284
Requested session ID = {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94285
Requested session ID is from cookie.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94286
Requested session ID is not from cookie.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94287
Requested session ID is valid.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94288
Requested session ID is invalid.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94289
Session was not created by Oracle Forms.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94302
Encountering {0} while attempting to proxy the Oracle Internet Directory connection to the SSO user.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94332
Starting session in SSO mode. Details: {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94334
User name from Oracle Internet Directory: {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94398
SAA: Javascript sent to launched browser: {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94430
Trying to get a prestarted process.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94431
Prestarted process is available and selected.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94432
Prestarted process is not available.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94433
prestart archive file does not exist

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94522
Creating new runtime process using default executable.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94523
Creating new runtime process using executable "{0}".

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94532
RunformProcess.startProcess(): executing {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94533
RunformProcess.startProcess(): execution failure, trying again using {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94538
successful creation of new runtime process

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94542
Getting stderr of child process.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94547
port number from message: {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94554
successful connection to runtime process after {0} attempts

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94556
successful connection to runtime process at port {0}

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94562
RunformSession.valueUnbound(): stopping runtime process.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-94610
Read timeout. Sending Response Pending with retry time = {0}.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-96910
runtime process: OS page size is {0}.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-96911
runtime process: preferred file system block size for temporary record buffer file is {0}.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-96912
runtime process: page size for temporary record buffer file is {0}.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-96913
runtime process: record manager record segment size for block {0}.{1} is {2}, adjusted to {3}.

Category:
Other

Cause:
This message is intended primarily for Oracle Support Services.

Action:
No action is required.

FRM-99999
Error {0}: See the release notes file (relnotes) for information about this error.

Category:
Configuration

Cause:
See the release notes.

Action:
Take action as documented in the release notes.

12
GGSTU-60000 to GGSTU-65036

GGSTU-60000
Unable to deploy.

Category:
Deployment

Cause:
Error happened in OGG Studio while deploying.

Action:
Retry Deployment.

GGSTU-60001
Unable to deploy as rest api service failed.

Category:
Request

Cause:
OGG Rest Service for Process Status is down.

Action:
Restart OGG Manager and Jagent Process.

GGSTU-60002
Unable to deploy as rest api service failed.

Category:
Request

Cause:
OGG Rest Service for Monitoring Points is down.

Action:
Restart OGG Manager and Jagent Process.

GGSTU-60003
Unable to deployment OGG Instance Resource is not assigned.

Category:
Deployment

Cause:
Assignment is not done.

Action:
Do OGG Instance Resource assignment through Wizard or Drag and Drop from Resource Navigator.

GGSTU-60004
Unable to deploy. Data Server Resource is not assigned.

Category:
Deployment

Cause:
Assignment is not done.

Action:
Do Data Server Resource assignment through Wizard or Drag and Drop from Resource Navigator.

GGSTU-60005
Unable to delete trail file.

Category:
Deployment

Cause:
Some error is happening while deleting the trail file.

Action:
Please delete the old trail file manaully.

GGSTU-60006
Unable to connect to OGG Instance.

Category:
Deployment

Cause:
Jagent in OGG is down or configuration of OGG Instance Resource is wrong.

Action:
Please check Jagent should be running in OGG or check configuraion of OGG Instance Resource.

GGSTU-60007
Unable to create root or temp directory

Category:
Deployment

Cause:
The root directory of oracledi and temp directory inside could not be verified.

Action:
Please check to see if the directory oracledi and temp directory inside it are accessible.

GGSTU-60008
Unable to process obey header template file

Category:
Deployment

Cause:
The file /oracle/oggstudio/deploy/resources/templateHeader.vm may have accessibility issues.

Action:
Please retry.

GGSTU-60009
Unable to take backup of the file

Category:
Deployment

Cause:
Error in the taking backup of prm or obey file.

Action:
Please start/stop jagent process and redeploy.

GGSTU-60010
Unable to deploy Oracle Data Pump Initial Load

Category:
Deployment

Cause:
Selected Database is not Oracle.

Action:
Please use Oracle Database.

GGSTU-60050
Rest Service failure. Unable to open connection to REST service

Category:
Deployment

Cause:
Failure in connecting to REST service.

Action:
Please check to see REST service is up. Check to see if the URL used to connect to REST service is correct.

GGSTU-60051
Rest Service failure. Unable to get status

Category:
Deployment

Cause:
Error in parsing of status response received from REST service.

Action:
Please check to see REST service is up and sending correct format response for status.

GGSTU-60052
Rest Service failure. Unable to get monitorying data.

Category:
Deployment

Cause:
Error in parsing of Monitoring data response received from REST service.

Action:
Please check to see REST service is up and sending correct format response for monitoring.

GGSTU-60053
Unable to synchronize profile

Category:
Deployment

Cause:
Error while synchronizing profiles with solution.

Action:
Please refresh Project navigator and try again.

GGSTU-60054
Unable to create diroby directory in OGG Instance.

Category:
Deployment

Cause:
Error while creating diroby directory in OGG Instance.

Action:
Please update installed Jagent or create diroby directory manaully.

GGSTU-60200
Unable to start/stop process.

Category:
UI

Cause:
Error in starting or stoping process.

Action:
Please check if the JAgent service is up and running.

GGSTU-60201
Unable to create deployment archive.

Category:
UI

Cause:
Error in creating deployment archive.

Action:
Critical error UI after creation of deployment archive failed.

GGSTU-60202
Unable to do online deployment.

Category:
UI

Cause:
Error in executing job of online deployment.

Action:
Critical error UI after job of online deployment failed.

GGSTU-60203
Unable to create deployment agent dialog box.

Category:
UI

Cause:
Error in showing dialog box for deployment agent.

Action:

GGSTU-60250
Framework error in opening a CEF editor.

Category:
UI

Cause:
Error in initializing the UI for a CEF editor.

Action:
Critical error in UI module in opening a CEF editor.

GGSTU-60251
Framework error in closing a CEF editor.

Category:
UI

Cause:
Error in closure of the UI for a CEF editor.

Action:
Critical error in UI module in closing a CEF editor.

GGSTU-60300
Error while adding a page to the panel for the Initial load wizard.

Category:
WIZARD

Cause:
Exception while adding page to the Initial load panel wizard.

Action:
Page addition to Initial load wizard failed. Check to see if the Initial load is configured properly.

GGSTU-60301
Error while adding a page to the panel for the Instance assignment wizard.

Category:
WIZARD

Cause:
Exception while adding page to the Instance assignment wizard.

Action:
Page addition to Instance Assignemnt wizard failed. Check to see if the Instances are configured properly.

GGSTU-60302
Error while adding a page to the panel for the Data Server assignment wizard.

Category:
WIZARD

Cause:
Exception while adding page to the Data Server assignment wizard.

Action:
Page addition to Data Server Assignemnt wizard failed. Check to see if the Data Servers are configured properly.

GGSTU-61000
Addin failed to initialize.

Category:
UI

Cause:
Exception while trying to initialize the Studio addin.

Action:
The addin failed. Try to restart the application.

GGSTU-61001
Exception while checking if CEF node can be duplicated

Category:
UI

Cause:
Exception while trying to check if the CEF node can be duplicated.

Action:

GGSTU-61002
Exception while handling duplicate CEF node event.

Category:
UI

Cause:
Exception while trying to process the duplicate CEF node event.

Action:

GGSTU-61003
Exception while handling repository export event.

Category:
UI

Cause:
Exception while trying to process the repository export event.

Action:

GGSTU-61004
Exception while handling repository import event.

Category:
UI

Cause:
Exception while trying to process the repository import event.

Action:

GGSTU-61100
Overall exception in loading metadata for OGG Studio.

Category:
UI

Cause:
Generic Exception in loading metadata.

Action:
Overall failure of loading metadata. Please check for other error codes for specific action.

GGSTU-61101
Exception in loading resource bundle of metadata for OGG Studio.

Category:
UI

Cause:
Error during loading resource bundle for meta data.

Action:
Please check and see if the resource bundle for meta data is present in correct location.

GGSTU-61102
Exception in parsing the metadata xml for OGG Studio.

Category:
UI

Cause:
Error during parking the meta data file.

Action:
Please check and see if the format of meta data file is correct. Check for any missing tags etc.

GGSTU-61103
Exception in reading the metadata properties file for OGG Studio.

Category:
UI

Cause:
Error during reading the meta data properties file.

Action:
Please check and see if the meta data properties file is present at the correct location. Also check if the directory has correct permissions.

GGSTU-61104
Exception in reading and parsing the metadata xml file for OGG Studio.

Category:
UI

Cause:
Error during reading and parsing the meta data xml file.

Action:
Please check and see if the meta data xml file is present at the correct location. Also check if the directory has correct permissions. Also check for any missing tags in the xml file.

GGSTU-64000
Connection context creation failure. Unable to get OGG Resources connection context.

Category:
Resources

Cause:
Error while getting OGG Resources Connection context

Action:
Please make sure connection context configuration is correct

GGSTU-64001
Unable to destroy adf connection context.

Category:
Resources

Cause:
Error while destroying adf connection context.

Action:
Please make sure connection context exists and the user has permissions to destroy the context.

GGSTU-64002
JNDI Context creation failure. Unalbe to create jndi context.

Category:
Resources

Cause:
Error while creating jndi context.

Action:
Please make sure JNDI configuration is correct.

GGSTU-64003
ADF Config creation failure. Unable to create adf config files.

Category:
Resources

Cause:
Error while creating adf config files.

Action:
Please make sure PROVIDER URL is correctly configured.

GGSTU-64004
Unable to create adf connection context document

Category:
Resources

Cause:
Error while creating adf connection context document.

Action:
Please make sure ADF connection context is configured correctly.

GGSTU-64005
JNDI Context initialization failure. Unable to initialize JNDI context factory.

Category:
Resources

Cause:
Error while initializing jndi context.

Action:
Please make sure JNDI is correctly configured.

GGSTU-64006
Resource save failure. Unable to save resource in adf config.

Category:
Resources

Cause:
Error while saving resource in adf config.

Action:
Kindly retry by using a different resource name. Also, make sure all the resource parameters are correct.

GGSTU-64007
Resource persist failure. Unable to save/persist resource in repository.

Category:
Resources

Cause:
Error while saving resource in repository

Action:
Please try to use a different resource name. Also, make sure that the parameters of resource are correct.

GGSTU-64008
Resource already exists in repository.

Category:
Resources

Cause:
Resource already exists in repository.

Action:
Please use a different resource name.

GGSTU-64009
Resource not found error. Unable to find the specified resource

Category:
Resources

Cause:
Error while retrieving the resource.

Action:
Please use a resource that exists in repository.

GGSTU-64010
Resource Modification failure. Not able to modify/update the specified resource.

Category:
Resources

Cause:
Error while updating the resource.

Action:
Please retry with different properties of resource. Some of the values modifed might be incorrect.

GGSTU-64011
Resource deletion failure. Not able to delete the specified resource.

Category:
Resources

Cause:
Error while deleting resource

Action:
Please make sure this resource is not used by some other object. Kindly delete any association of this resource with others before trying again.

GGSTU-64012
Unable to load adf context document.

Category:
Resources

Cause:
Error while loading adf context document

Action:
Please make sure the adf configuration is correctly configured.

GGSTU-64013
Unable to copy mapping group to global resource library

Category:
Resources

Cause:
Error while copying mapping group to Global Resource Library

Action:
Please make sure that a resource with same name does not currenlty exist. Kindly retry.

GGSTU-64014
OGG Instance name must have text; it must not be empty or blank.

Category:
Resources

Cause:
Error while creating resource

Action:
Please make sure this Instance name is provided in Name field

GGSTU-64015
Unable to find if the data server is assigned to any solution. Data server cannot be renamed.

Category:
Resources

Cause:
Error while trying to find if the data server is assigned to any solution.

Action:
Please create another data server connection with the desired name.

GGSTU-65010
Unable to open the Conflict Resolution edit dialog

Category:
PI

Cause:
Component definition file is missing.

Action:
Make sure component definition file exists in the location

GGSTU-65011
Unable to open the edit dialog

Category:
PI

Cause:
Component definition file is missing.

Action:
Make sure component definition file exists in the location

GGSTU-65012
Failed to open the component panel.

Category:
PI

Cause:
Component definition file is missing or component file has error.

Action:
Make sure component definition file exists in the location

GGSTU-65013
Unable to initialize the component.

Category:
PI

Cause:
Component definition file is missing or component file has error.

Action:
Make sure component definition file exists in the location

GGSTU-65030
Unable to get the node graphic

Category:
Diagram Node

Cause:
Unable to read/write the stream

Action:
Make sure that read/write permission is available or the file exists

GGSTU-65031
Invalid destination

Category:
Diagram Node

Cause:
Invalid Target

Action:
Please select a valid destination

GGSTU-65032
Unable to get the graph

Category:
Diagram Node

Cause:
The controller is not available.

Action:
Make sure the controller exists

GGSTU-65033
Unable to assign the source

Category:
Diagram Node

Cause:
Invalid source selected

Action:
Make sure that the selected source is valid

GGSTU-65034
Unable to delete the node

Category:
Diagram Node

Cause:
Controller is not valid

Action:
Make sure the controller is valid

GGSTU-65035
Unable to attach the model to the graphic

Category:
Diagram Node

Cause:
model is not available or does not exist

Action:
Make sure that the model for the graphic available.

GGSTU-65036
Unable layout the diagram

Category:
Diagram Node

Cause:
layout failed due to various reasons.

Action:

13
IAM-0010002 to IAM-90400084

IAM-0010002
Error occurred while creating an organization.

Category:
Logging

Cause:

Action:

IAM-0010006
Error occurred while deleting an organization.

Category:
Logging

Cause:

Action:

IAM-0010010
Error occurred while updating an organization.

Category:
Logging

Cause:

Action:

IAM-0010011
Error occurred while enabling an organization.

Category:
Logging

Cause:

Action:

IAM-0010012
Error occurred while disabling an organization.

Category:
Logging

Cause:

Action:

IAM-0011005
User with key "{0}" does not exist.

Category:
Logging

Cause:

Action:

IAM-0011006
Error occurred while deleting an user "{0}".

Category:
Logging

Cause:

Action:

IAM-0011009
Please check date format. Valid format should be - {0}

Category:
Logging

Cause:

Action:

IAM-0011011
Error occurred while enabling an user "{0}".

Category:
Logging

Cause:

Action:

IAM-0011015
Error occurred while enabling bulk users.

Category:
Logging

Cause:

Action:

IAM-0011017
Error occurred while deleting bulk users.

Category:
Logging

Cause:

Action:

IAM-0011018
Password did not match.

Category:
Logging

Cause:

Action:

IAM-0011019
An error occurred while verifying password for User "{0}".

Category:
Logging

Cause:

Action:

IAM-0011020
An error occurred while retrieving password for User "{0}".

Category:
Logging

Cause:

Action:

IAM-0011021
An error occurred while resetting password for User "{0}".

Category:
Logging

Cause:

Action:

IAM-0011022
Invalid data type of "{0}" MLS attribute value.

Category:
Logging

Cause:

Action:

IAM-0011023
Could not get DB connection from repository.

Category:
Logging

Cause:

Action:

IAM-0011024
Search where condition failed

Category:
Logging

Cause:

Action:

IAM-0011025
An error occurred while retrieving challenge questions and answers for User "{0}".

Category:
Logging

Cause:

Action:

IAM-0011026
An error occurred while deleting challenge questions and answers for User "{0}".

Category:
Logging

Cause:

Action:

IAM-0012002
Error occurred while creating a role.

Category:
Logging

Cause:

Action:

IAM-0012005
Role with key "{0}" does not exist.

Category:
Logging

Cause:

Action:

IAM-0012016
Error occurred while modifying bulk roles.

Category:
Logging

Cause:

Action:

IAM-0012017
Error occurred while deleting bulk roles.

Category:
Logging

Cause:

Action:

IAM-0012102
Error occurred while creating a role category.

Category:
Logging

Cause:

Action:

IAM-0012105
Role Category with key "{0}" does not exist.

Category:
Logging

Cause:

Action:

IAM-0012106
Error occurred while deleting a role category.

Category:
Logging

Cause:

Action:

IAM-0012110
Error occurred while modifying a role category.

Category:
Logging

Cause:

Action:

IAM-0012202
Error occurred while creating a role grant.

Category:
Logging

Cause:

Action:

IAM-0012206
Error occurred while deleting a role grant.

Category:
Logging

Cause:

Action:

IAM-0012207
Error occurred while modifying a role grant.

Category:
Logging

Cause:

Action:

IAM-0012208
Error occurred while creating and deleting role grants.

Category:
Logging

Cause:

Action:

IAM-0012302
Error occurred while creating a role relationship.

Category:
Logging

Cause:

Action:

IAM-0012306
Error occurred while deleting a role relationship.

Category:
Logging

Cause:

Action:

IAM-0012307
Error occurred while modifying a role relationship.

Category:
Logging

Cause:

Action:

IAM-0020006
The returned list of OIM role for the logged in user is {0}

Category:
Logging

Cause:

Action:

IAM-0020007
Not able to get the roles for the given user {0}

Category:
Logging

Cause:

Action:

IAM-0020009
Crypto error encountered while trying to login as admin {0}

Category:
Logging

Cause:

Action:

IAM-0020010
IOException thrown while trying to login as admin {0}

Category:
Logging

Cause:

Action:

IAM-0020011
Login Exception encountered when trying to login as admin {0}

Category:
Logging

Cause:

Action:

IAM-0020012
Exception encountered while trying to login as admin {0}

Category:
Logging

Cause:

Action:

IAM-0020013
An error occurred while trying to notify server that a new login session has been created.

Category:
Logging

Cause:

Action:

IAM-0020014
An error occurred while trying to notify server that a login session has been destroyed.

Category:
Logging

Cause:

Action:

IAM-0020015
JpsException encountered while asserting/logging in as user {0} : {1}

Category:
Logging

Cause:

Action:

IAM-0020016
AssertionException encountered while asserting/logging in as user {0} : {1}

Category:
Logging

Cause:

Action:

IAM-0020017
PrivilegedActionException encountered while asserting/logging in as user {0} : {1}

Category:
Logging

Cause:

Action:

IAM-0030000
An error occurred while creating document builder.

Category:
Logging

Cause:

Action:

IAM-0030001
An error occurred while unwrapping object in context aware.

Category:
Logging

Cause:

Action:

IAM-0030003
An error occurred while initializing anonymous user.

Category:
Logging

Cause:

Action:

IAM-0030004
An error occurred while creating object in context manager.

Category:
Logging

Cause:

Action:

IAM-0030005
An error occurred while loading from proxy in context manager.

Category:
Logging

Cause:

Action:

IAM-0030006
An error occurred while setting user details in context manager.

Category:
Logging

Cause:

Action:

IAM-0030007
An error occurred while loading wrapped context in context manager.

Category:
Logging

Cause:

Action:

IAM-0040000
Cannot load entity definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040001
Cannot create MDS instance/session - {0}

Category:
Logging

Cause:

Action:

IAM-0040002
Cannot load metadata - {0}

Category:
Logging

Cause:

Action:

IAM-0040003
Loading entity definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040004
Cannot initialize repository - {0}

Category:
Logging

Cause:

Action:

IAM-0040005
Initializing repository - {0} of type {1}

Category:
Logging

Cause:

Action:

IAM-0040006
Cannot load relation definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040007
Loading relation definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040008
Loading repository definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040009
Cannot load repository definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040010
Loading data provider definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040011
Cannot load data provider definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040012
Loading data type definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040013
Cannot load data type definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040014
Loading derived data type definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040015
Cannot load derived data type definition - {0}

Category:
Logging

Cause:

Action:

IAM-0040016
Initializing data provider for entity type - {0} of type {1}

Category:
Logging

Cause:

Action:

IAM-0040017
Cannot initialize data provider - {0}

Category:
Logging

Cause:

Action:

IAM-0040018
Cannot register MDS change notification listener - {0}

Category:
Logging

Cause:

Action:

IAM-0040019
Reloading metadata due to changes to metadata

Category:
Logging

Cause:

Action:

IAM-0040020
Cannot load child entity - {0} from {1} to {2} - {3}

Category:
Logging

Cause:

Action:

IAM-0040021
Cannot load entity attributes - {0}

Category:
Logging

Cause:

Action:

IAM-0040022
Failed to load XML schema, XML schema validation will be bypassed - {0}

Category:
Logging

Cause:

Action:

IAM-0040023
XML schema validation failed for {0} - {1}

Category:
Logging

Cause:

Action:

IAM-0040024
Performing XML schema validation on {0}

Category:
Logging

Cause:

Action:

IAM-0040025
Failed to initialize JAXB unmarshaller - {0}

Category:
Logging

Cause:

Action:

IAM-0040026
Initializing relation provider for relation type - {0} of type {1}

Category:
Logging

Cause:

Action:

IAM-0040027
Cannot initialize relation provider - {0}

Category:
Logging

Cause:

Action:

IAM-0040028
Cannot load relation attributes - {0}

Category:
Logging

Cause:

Action:

IAM-0040029
Cannot load relations - {0}

Category:
Logging

Cause:

Action:

IAM-0040031
An error occurred while trying to generate object.

Category:
Logging

Cause:

Action:

IAM-0040032
An error occurred while trying to get attribute definition.

Category:
Logging

Cause:

Action:

IAM-0040033
An error occurred while trying to modify bulk entity.

Category:
Logging

Cause:

Action:

IAM-0040034
Audit error: Failed to audit operation {0} for entityType {1} with key {2} due to error: {3}

Category:
Logging

Cause:

Action:

IAM-0040035
Audit error: Failed to fetch old entity data for entity {0} due to {1}

Category:
Logging

Cause:

Action:

IAM-0040036
Audit error: Failed to search for relation between {0} {1} and {2} {3} for operation {4} due to {5}

Category:
Logging

Cause:

Action:

IAM-0040037
Audit error: Failed to fetch entity name for entity {0} {1} for operation {2} due to {3}

Category:
Logging

Cause:

Action:

IAM-0040038
Audit error: Failed to get the data type of attribute {0} for entity {1} due to {2}

Category:
Logging

Cause:

Action:

IAM-0040039
Audit error: Failed to audit operation {0} due to error: {3}

Category:
Logging

Cause:

Action:

IAM-0040040
Audit error: Failed to transform data for attribute {0} for entityType {1} due to error: {2}

Category:
Logging

Cause:

Action:

IAM-0042001
An error occurred while initializing the LDAP data provider, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042002
An error occurred while creating the entity in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042003
An error occurred while reserving the user in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042004
An error occurred while un-reserving the user in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042005
An error occurred while modifying the entity in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042006
An error occurred while looking up the entity in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042007
An error occurred while removing the entity in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042008
An error occurred while searching the entity in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042009
An error occurred while resetting the user password in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042010
An error occurred while enabling the user in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042011
An error occurred while disabling the user in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042012
An error occurred while checking if the user is enabled in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042013
An error occurred while locking the user in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042014
An error occurred while unlocking the user in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042015
An error occurred while checking if the user is locked in LDAP, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0042016
An error occurred while getting the change log from LDAP - {0}

Category:
Logging

Cause:

Action:

IAM-0042018
Entity creation of entity type {0} failed because it exists in LDAP.

Category:
Logging

Cause:

Action:

IAM-0042019
Entity creation of entity type {0} failed in LDAP directory because of a unique constraint violation.

Category:
Logging

Cause:

Action:

IAM-0042020
{0} operation failed because the role {1} does not exist in LDAP.

Category:
Logging

Cause:

Action:

IAM-0042021
Unable to get LDAP connection, and the root cause is - {0}

Category:
Logging

Cause:

Action:

IAM-0042022
An error occurred while checking if user entity got reserved in LDAP. Please verify and cleanup manually under LDAP reserve container.

Category:
Logging

Cause:

Action:

IAM-0042024
{0} operation failed because the user {1} does not exist in LDAP.

Category:
Logging

Cause:

Action:

IAM-0042025
{0} deletion operation failed because the role {1} does not exist in LDAP.

Category:
Logging

Cause:

Action:

IAM-0042026
{0} deletion operation failed because the user {1} does not exist in LDAP.

Category:
Logging

Cause:

Action:

IAM-0042027
An error occurred while getting the change log from LDAP. Results upto this last Change Number {0} have been retrieved and processed before an error occurred.

Category:
Logging

Cause:

Action:

IAM-0042028
Entity creation of entity type {0} failed: The parent container of the DN {1} does not exist in LDAP.

Category:
Logging

Cause:

Action:

IAM-0044001
Unable to close connection.

Category:
Logging

Cause:

Action:

IAM-0044003
Invalid SearchCriteria for 'where' contition

Category:
Logging

Cause:

Action:

IAM-0044004
Parameter {0} is mandatory in search API.

Category:
Logging

Cause:

Action:

IAM-0044006
Provider definition for {0} provider type is not found.

Category:
Logging

Cause:

Action:

IAM-0050000
Error occurred while executing unmanaged async task. Task Name:{0}

Category:
Logging

Cause:

Action:

IAM-0050001
Error occurred while executing managed async task. Task Name:{0}, InstanceID:{1}, Category: {2}

Category:
Logging

Cause:

Action:

IAM-0050002
Exception occurred while parsing async messaging configuration.

Category:
Logging

Cause:

Action:

IAM-0050003
Failed to load async messaging configuration. Please check the async-messaging.xml is present in <OIM_HOME>/metadata/file directory

Category:
Logging

Cause:

Action:

IAM-0050004
Retry failed for FailedTask with ID:{0}, TaskName:{1}, InstanceID:{2}, Category:{3}

Category:
Logging

Cause:

Action:

IAM-0050005
Error while processing JMS Message

Category:
Logging

Cause:

Action:

IAM-0050006
Invalid async messaging configuration. XML Schema Validation Failed

Category:
Logging

Cause:

Action:

IAM-0050007
The XML Schema for Async Configuration {0} was not found. XML Validation will be skipped

Category:
Logging

Cause:

Action:

IAM-0050008
Failed to load async messaging configuration.Please check if {0} is present in OIM_HOME/metadata directory

Category:
Logging

Cause:

Action:

IAM-0050009
Please check the discovery config value for backOfficeURL.

Category:
Logging

Cause:

Action:

IAM-0050010
Error Trace Follows

Category:
Logging

Cause:

Action:

IAM-0050012
An error occurred while trying get context value.

Category:
Logging

Cause:

Action:

IAM-0060007
The mapper plugin ID in configuration client is {0}

Category:
Logging

Cause:

Action:

IAM-0060009
Mapping was not successful.

Category:
Logging

Cause:

Action:

IAM-0060010
Error while loading mapping plugin

Category:
Logging

Cause:

Action:

IAM-0060011
Error while setting authentication context in oim

Category:
Logging

Cause:

Action:

IAM-0060012
Inside init of authentication filter

Category:
Logging

Cause:

Action:

IAM-0060021
Login failed for userid {0}

Category:
Logging

Cause:

Action:

IAM-0060025
OIM User is {0}

Category:
Logging

Cause:

Action:

IAM-0060027
Client context should not be null

Category:
Logging

Cause:

Action:

IAM-0060036
An error occurred while trying to get group display name.

Category:
Logging

Cause:

Action:

IAM-0060037
An error occurred while trying to get group security name.

Category:
Logging

Cause:

Action:

IAM-0060039
An error occurred while trying to get groups ids.

Category:
Logging

Cause:

Action:

IAM-0060040
Unable to initialize pool data source.

Category:
Logging

Cause:

Action:

IAM-0060041
An error occurred while trying to set SQL Hint.

Category:
Logging

Cause:

Action:

IAM-0060042
An error occurred while trying to close DB connection.

Category:
Logging

Cause:

Action:

IAM-0060043
An error occurred while trying to get user name.

Category:
Logging

Cause:

Action:

IAM-0060044
User {0} locked at {1}.

Category:
Logging

Cause:

Action:

IAM-0060045
Error while locking user {0}.

Category:
Logging

Cause:

Action:

IAM-0060046
Error while clearing login attempts for user {0}.

Category:
Logging

Cause:

Action:

IAM-0060047
Error while increasing login attempts for user {0}.

Category:
Logging

Cause:

Action:

IAM-0060048
Property {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-0060049
Error while retrieving property {0}.

Category:
Logging

Cause:

Action:

IAM-0060050
Error while fetching groups for pattern.

Category:
Logging

Cause:

Action:

IAM-0060051
Error while retrieving user key {0}.

Category:
Logging

Cause:

Action:

IAM-0060052
Error while getting lookup details.

Category:
Logging

Cause:

Action:

IAM-0060053
Error while updating successful login date for user {0}.

Category:
Logging

Cause:

Action:

IAM-0070000
An error occurred while loading the logging resource bundle {0}

Category:
Logging

Cause:

Action:

IAM-0070001
An error occurred while finding the invoking class.

Category:
Logging

Cause:

Action:

IAM-0070002
An error occurred while finding the invoking package.

Category:
Logging

Cause:

Action:

IAM-0070003
The class name of the logging resource bundle must be LRB.

Category:
Logging

Cause:

Action:

IAM-0070004
The package name of logging resource bundle must be resources.

Category:
Logging

Cause:

Action:

IAM-0070016
An error occurred while initializing service : {0}

Category:
Logging

Cause:

Action:

IAM-0070022
An error occurred while doing eclipselink cache co-ordination initialization in this clustered environment and corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0070023
Could not get logger for {0}. Returning the logger without using LRB.

Category:
Logging

Cause:

Action:

IAM-0070024
An error occurred while setting the eclipselink cache co-ordination discovery address - {0}

Category:
Logging

Cause:

Action:

IAM-0070025
Eclipselink cache co-ordination discovery address - {0}

Category:
Logging

Cause:

Action:

IAM-0070026
Entering method {0} of class {1} with arguments {2}

Category:
Logging

Cause:

Action:

IAM-0070027
Exiting method {0} of class {1} with return value {2}

Category:
Logging

Cause:

Action:

IAM-0071000
An error occurred while reading a file.

Category:
Logging

Cause:

Action:

IAM-0073000
An error occurred while initializing the cache {0}

Category:
Logging

Cause:

Action:

IAM-0074000
XML schema validation warning - Col={0}, Line={1} - {2}

Category:
Logging

Cause:

Action:

IAM-0074001
XML schema validation error - Col={0}, Line={1} - {2}

Category:
Logging

Cause:

Action:

IAM-0074002
XML schema validation fatal error - Col={0}, Line={1} - {2}

Category:
Logging

Cause:

Action:

IAM-0075000
Invalid lookup query. Query does not begin with 'SELECT' clause

Category:
Logging

Cause:

Action:

IAM-0075001
Invalid lookup query. Query does not have 'FROM' clause

Category:
Logging

Cause:

Action:

IAM-0075002
Invalid lookup query. Query has '*' clause

Category:
Logging

Cause:

Action:

IAM-0076000
oim-config.xml was not found in MDS Repository.

Category:
Logging

Cause:

Action:

IAM-0076001
Unable to find keystore "{0}" in <DOMAIN_HOME>/config/fmwconfig/.

Category:
Logging

Cause:

Action:

IAM-0076002
Password for {0} is not seeded in CSF.

Category:
Logging

Cause:

Action:

IAM-0076003
OIM application initialization failed because of the following reasons:

Category:
Logging

Cause:

Action:

IAM-0076004
Unable to map the credentials.

Category:
Logging

Cause:

Action:

IAM-0076005
Unable to determine application server type.

Category:
Logging

Cause:

Action:

IAM-0077000
An error occurred while retrieving credentials for appid.

Category:
Logging

Cause:

Action:

IAM-0077001
An error occurred while getting service instance of credential store.

Category:
Logging

Cause:

Action:

IAM-0077002
An error occurred while getting password.

Category:
Logging

Cause:

Action:

IAM-0077003
An error occurred while getting generic credential.

Category:
Logging

Cause:

Action:

IAM-0077004
An error occurred while getting user.

Category:
Logging

Cause:

Action:

IAM-0077005
An error occurred while setting password.

Category:
Logging

Cause:

Action:

IAM-0078002
Make sure that {0} is serializable.

Category:
Logging

Cause:

Action:

IAM-0078003
Make sure that your session objects do directly or indirectly have instance variable of type {0}.

Category:
Logging

Cause:

Action:

IAM-0079000
An error occurred while executing LDAPConfigAutomationTool and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0079001
An error occurred while preconfiguring Directory in LDAPConfigAutomationTool and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-0079002
prepareidstore not complete and system admin dn used

Category:
Logging

Cause:

Action:

IAM-0079003
prepareidstore not complete

Category:
Logging

Cause:

Action:

IAM-0079006
The following properties are null or empty - {0}

Category:
Logging

Cause:

Action:

IAM-0079007
Enter User Password for {0}:

Category:
Logging

Cause:

Action:

IAM-0079008
Confirm User Password for {0}:

Category:
Logging

Cause:

Action:

IAM-0079009
The passwords do not match. Please re-enter.

Category:
Logging

Cause:

Action:

IAM-0079010
File not found - {0}

Category:
Logging

Cause:

Action:

IAM-0079011
Error in reading password file - {0}

Category:
Logging

Cause:

Action:

IAM-0079012
Error parsing the arguments

Category:
Logging

Cause:

Action:

IAM-0079013
Usage:- prepareIDStore.sh -prepareIDStore [-options -v pwd_file=<filename> log_level=<level>] where -prepareIDStore = [Required] performs Directory configuration and seeding -v = [Optional] Verbose mode; gives an overview of operations for prepareIDStore.sh -prepareIDStore command without performing any actual write operations in the Directory pwd_file = [Optional] File to provide password Sample Usage: prepareIDStore.sh -prepareIDStore -v pwd_file=filename.txt NOTE: Use idstore-automate-install.properties to specify values for Directory Configuration

Category:
Logging

Cause:

Action:

IAM-0079014
Validation for Directory Server details failed with following error(s) - {0}

Category:
Logging

Cause:

Action:

IAM-0079015
Loading file - {0} ...

Category:
Logging

Cause:

Action:

IAM-0079016
DN does not exist - {0}

Category:
Logging

Cause:

Action:

IAM-0079017
Connection to Directory Locked: Check Host/Port/Bind Credentials

Category:
Logging

Cause:

Action:

IAM-0079018
Preconfiguring Directory Failed. Cannot find user entry for user login:

Category:
Logging

Cause:

Action:

IAM-0079019
Invalid option entered. For help, use -help

Category:
Logging

Cause:

Action:

IAM-0079020
LDAP server and/or credentials empty

Category:
Logging

Cause:

Action:

IAM-0079021
Container(s) value empty

Category:
Logging

Cause:

Action:

IAM-0079022
Verify LDAP connection details/LDAP container values

Category:
Logging

Cause:

Action:

IAM-0079023
For Active Directory, ldapConfigTool.sh -prepareIDStore should be executed first before executing OIM Configuration

Category:
Logging

Cause:

Action:

IAM-0079900
An error occurred while loading the parent resource bundle {0}

Category:
Logging

Cause:

Action:

IAM-0079901
An error occurred while obtaining the document builder to parse XMLs.

Category:
Logging

Cause:

Action:

IAM-0079902
An error occurred while parsing the XML document.

Category:
Logging

Cause:

Action:

IAM-0079903
The console is not available to accept input.

Category:
Logging

Cause:

Action:

IAM-0079904
An error occurred while accepting the password.

Category:
Logging

Cause:

Action:

IAM-0079905
Invalid datatype of MLS attribute value

Category:
Logging

Cause:

Action:

IAM-0079906
Invalid datatype of Old MLS attribute value

Category:
Logging

Cause:

Action:

IAM-0079907
A duplicate locale key entry for {0} found.

Category:
Logging

Cause:

Action:

IAM-0079908
Error occurred while fetching the Default Locale.

Category:
Logging

Cause:

Action:

IAM-0080001
An error occurred while executing the kernel event handler.

Category:
Logging

Cause:

Action:

IAM-0080008
An error occurred while loading the orchestration engine, and the corresponding message is - {0}

Category:
Logging

Cause:

Action:

IAM-0080013
Kernel executing default validation with process id, event id, entity and operation {0}.{1}.{2}.{3}

Category:
Logging

Cause:

Action:

IAM-0080014
Kernel executing default action handler with process id, event id, entity and operation {0}.{1}.{2}.{3}.entityId={4}

Category:
Logging

Cause:

Action:

IAM-0080015
Operation - {0} that is submitted as part of the orchestration is not supported.

Category:
Logging

Cause:

Action:

IAM-0080016
Creating entity with id - {0}

Category:
Logging

Cause:

Action:

IAM-0080017
Modifying entity with id - {0}

Category:
Logging

Cause:

Action:

IAM-0080018
Deleting entity with id - {0}

Category:
Logging

Cause:

Action:

IAM-0080019
Adding relation with participants ids - {0}

Category:
Logging

Cause:

Action:

IAM-0080020
Deleting relationship between participants - {0}

Category:
Logging

Cause:

Action:

IAM-0080026
Event handler {0} implemented using class/plug-in {1} could not be loaded.

Category:
Logging

Cause:

Action:

IAM-0080031
An event handler was not found for {0} stage.

Category:
Logging

Cause:

Action:

IAM-0080032
Multiple event handlers with name: {0} found for {1} stage.

Category:
Logging

Cause:

Action:

IAM-0080041
Event handler with Name = {0} already exists. Overriding.{1} with {2}

Category:
Logging

Cause:

Action:

IAM-0080042
Orchestration process is not in failed status to handle the failures - {0}

Category:
Logging

Cause:

Action:

IAM-0080052
An error occurred while reading metadata from the document - {0} from MDS.

Category:
Logging

Cause:

Action:

IAM-0080054
XML validation error and the error message is - {0}. Error on Column Number={1},Line Number={2}

Category:
Logging

Cause:

Action:

IAM-0080055
No event handler loaded, XML validation fatal error and the error message is - {0}. Error on Column Number={1},Line Number={2}

Category:
Logging

Cause:

Action:

IAM-0080056
Normal flow of the orchestration process = {0}

Category:
Logging

Cause:

Action:

IAM-0080057
Schema is null, validation will not happen.

Category:
Logging

Cause:

Action:

IAM-0080058
XML validation warning - {0}. Warning on Column Number={1},Line Number={2}

Category:
Logging

Cause:

Action:

IAM-0080059
Plugin framework failed to load {0} with exception : {1}

Category:
Logging

Cause:

Action:

IAM-0080060
Failed to load default {0} handler for target {1}

Category:
Logging

Cause:

Action:

IAM-0080061
Error registering MDS change notification listener - {0}

Category:
Logging

Cause:

Action:

IAM-0080062
Unknown error

Category:
Logging

Cause:

Action:

IAM-0080072
XML schema validation warning - Col={0}, Line={1} - {2}

Category:
Logging

Cause:

Action:

IAM-0080073
XML schema validation error - Col={0}, Line={1} - {2}

Category:
Logging

Cause:

Action:

IAM-0080074
XML schema validation fatal error - Col={0}, Line={1} - {2}

Category:
Logging

Cause:

Action:

IAM-0080075
XML schema validation failed for XML {0} and it will not be loaded by kernel.

Category:
Logging

Cause:

Action:

IAM-0080076
An error occurred while computing user {0} preferences and corresponding error is {1}

Category:
Logging

Cause:

Action:

IAM-0080078
An error occurred while trying to register notification listener for plugin.

Category:
Logging

Cause:

Action:

IAM-0089999
Kernel Information: {0}

Category:
Logging

Cause:

Action:

IAM-0090000
Null agency for the current thread

Category:
Logging

Cause:

Action:

IAM-0091000
Constructing failure

Category:
Logging

Cause:

Action:

IAM-0091001
Finalizing failure

Category:
Logging

Cause:

Action:

IAM-0091100
Loading translation from {0}

Category:
Logging

Cause:

Action:

IAM-0091101
Cannot load translation

Category:
Logging

Cause:

Action:

IAM-0091102
Loading configuration from {0}

Category:
Logging

Cause:

Action:

IAM-0091103
Cannot load configuration

Category:
Logging

Cause:

Action:

IAM-0091104
Loading style sheet from {0}

Category:
Logging

Cause:

Action:

IAM-0091105
Cannot load style sheet

Category:
Logging

Cause:

Action:

IAM-0091106
Cannot load custom bundle

Category:
Logging

Cause:

Action:

IAM-0091107
Cannot find ConnectorResources directory in the installation directory.

Category:
Logging

Cause:

Action:

IAM-0091108
{0} is not a valid connector resource file.

Category:
Logging

Cause:

Action:

IAM-0091109
Connector resource bundle is not defined for the file: {0}

Category:
Logging

Cause:

Action:

IAM-0091110
An error occurred while creating connector resource bundle Object for: {0}

Category:
Logging

Cause:

Action:

IAM-0091113
Required parameter(s) missing. Either lookup query, save field, display field is not configured.

Category:
Logging

Cause:

Action:

IAM-0091114
An error occurred in lookup query. Please check the configured lookup query.

Category:
Logging

Cause:

Action:

IAM-0091115
An error occurred while executing the lookup query.

Category:
Logging

Cause:

Action:

IAM-0091116
An error occurred while executing the lookup query: {0}.

Category:
Logging

Cause:

Action:

IAM-0092010
Cannot get configurable {0}

Category:
Logging

Cause:

Action:

IAM-0093000
Sending failure

Category:
Logging

Cause:

Action:

IAM-0100100
An error occurred while retrieving menu permissions for user with id {0}.

Category:
Logging

Cause:

Action:

IAM-0100101
An error occurred while using the plugin for menu permissions.

Category:
Logging

Cause:

Action:

IAM-0100500
No menu items assigned for user with id {0}

Category:
Logging

Cause:

Action:

IAM-0120001
Entering Method {0}

Category:
Logging

Cause:

Action:

IAM-0120002
Exiting Method {0}

Category:
Logging

Cause:

Action:

IAM-0120003
Admin logged in.

Category:
Logging

Cause:

Action:

IAM-0120005
Creating a new Attribute Category for User attributes related to Multi-Tenancy.

Category:
Logging

Cause:

Action:

IAM-0120006
Adding Tenant GUID.

Category:
Logging

Cause:

Action:

IAM-0120007
Adding Tenant Name.

Category:
Logging

Cause:

Action:

IAM-0120008
Updating LDAP Sync mapping for User Login attributes.

Category:
Logging

Cause:

Action:

IAM-0120009
Creating a new Attribute Category for Role attributes related to Multi-Tenancy.

Category:
Logging

Cause:

Action:

IAM-0120010
Updating RDN Attribute.

Category:
Logging

Cause:

Action:

IAM-0120011
Updating LDAP Container Rule for MT.

Category:
Logging

Cause:

Action:

IAM-0120012
Adding Filter Parameters.

Category:
Logging

Cause:

Action:

IAM-0120013
Adding Filter Parameter Definitions.

Category:
Logging

Cause:

Action:

IAM-0120014
Configuring Recon Job {0}.

Category:
Logging

Cause:

Action:

IAM-0120015
Recon Job does not exist {0}.

Category:
Logging

Cause:

Action:

IAM-0120016
Job status succesfully changed to {0}.

Category:
Logging

Cause:

Action:

IAM-0120017
Last Change Number successfully updated to {0}.

Category:
Logging

Cause:

Action:

IAM-0120018
Updating scheduler type to Periodic.

Category:
Logging

Cause:

Action:

IAM-0120019
Job schedule type updated succesfully to Periodic.

Category:
Logging

Cause:

Action:

IAM-0120020
Existing trigger found.

Category:
Logging

Cause:

Action:

IAM-0120021
Creating new Trigger.

Category:
Logging

Cause:

Action:

IAM-0120022
Job interval changed succesfully to {0} minutes.

Category:
Logging

Cause:

Action:

IAM-0120024
Job Details after updating the configuration

Category:
Logging

Cause:

Action:

IAM-0120025
Schedule Type: {0}.

Category:
Logging

Cause:

Action:

IAM-0120026
Trigger Details:

Category:
Logging

Cause:

Action:

IAM-0120027
Exception while configuring recon jobs.

Category:
Logging

Cause:

Action:

IAM-0120028
Updating System Property {0} to true.

Category:
Logging

Cause:

Action:

IAM-0120029
Exception while configuring Job History Archival job.

Category:
Logging

Cause:

Action:

IAM-0120030
Dropping Index in DB.

Category:
Logging

Cause:

Action:

IAM-0120031
Creating Index in DB.

Category:
Logging

Cause:

Action:

IAM-0120032
Seeding APID user.

Category:
Logging

Cause:

Action:

IAM-0120035
Exception while seeding APPID user.

Category:
Logging

Cause:

Action:

IAM-1011000
Encountered exception {0}

Category:
Logging

Cause:

Action:

IAM-1011001
********** Entering the Authorization Segment with parameters:: LoggedInUserId = {0}, target resourceID = {1}, Feature = {2}, Action = {3} **********

Category:
Logging

Cause:

Action:

IAM-1011002
********** Exiting the Authorization Segment with result {0} **********

Category:
Logging

Cause:

Action:

IAM-1011003
Initialized the authorization service.

Category:
Logging

Cause:

Action:

IAM-1011004
Entering the method {0}

Category:
Logging

Cause:

Action:

IAM-1011005
Exiting the method {0}

Category:
Logging

Cause:

Action:

IAM-1011006
Adding the admin role {0} to the subject returned.

Category:
Logging

Cause:

Action:

IAM-1011010
Returning the map as {0}

Category:
Logging

Cause:

Action:

IAM-1011011
********** Entering the relationship grant check with parameters:: LoggedInUserId = {0}, beneficiarytype = {1}, beneficiaryId = {2}, targetEntityType = {3}, targetEntityId = {4} **********

Category:
Logging

Cause:

Action:

IAM-1011012
Entering the method {0} with parameters: LoggedInUserId = {1}, target resourceID = {2}, Feature = {3}, Action = {4}.

Category:
Logging

Cause:

Action:

IAM-1011013
Unable to publish entity.

Category:
Logging

Cause:

Action:

IAM-1011014
Published entity not found.

Category:
Logging

Cause:

Action:

IAM-1011015
Unable to update publications for entity : {0}.

Category:
Logging

Cause:

Action:

IAM-1011016
Unable to auto-publish entity of type : {0}

Category:
Logging

Cause:

Action:

IAM-1011017
EntityPublicationSearchCriteria cannot be null for search.

Category:
Logging

Cause:

Action:

IAM-1011018
No valid search criteria found for Entity publication search.

Category:
Logging

Cause:

Action:

IAM-1011019
Entity Publication: Unable to determine the lookup class for entity type : {0}. Defaulting to : {1}

Category:
Logging

Cause:

Action:

IAM-1011023
Unable to auto-publish. Logged in user details cannot be null.

Category:
Logging

Cause:

Action:

IAM-1011024
Unable to auto-publish. Nothing to publish.

Category:
Logging

Cause:

Action:

IAM-1011025
Unable to auto-publish. Cannot determine the entity-type : null.

Category:
Logging

Cause:

Action:

IAM-1011026
User {0} does not have permission for {1} on {2} with name : {3}

Category:
Logging

Cause:

Action:

IAM-1011027
Published entity details cannot be null.

Category:
Logging

Cause:

Action:

IAM-1011028
Scope for published entity cannot be null.

Category:
Logging

Cause:

Action:

IAM-1011029
The organization : {0} is not in ACTIVE state. Current status is {1}.

Category:
Logging

Cause:

Action:

IAM-1011030
Pagination parameter STARTROW cannot be greater or equal to ENDROW. STARTROW = {0}, ENDROW = {1}. Using Default values for fetch size :{2}

Category:
Logging

Cause:

Action:

IAM-1011031
Dont know how to enrich entity-type : {0} for entity publications.

Category:
Logging

Cause:

Action:

IAM-1011032
Skipping enrichment of non-Role publication object. Object found : {0}

Category:
Logging

Cause:

Action:

IAM-1011033
Dont know how to transform entity-type : {0} for entity publications.

Category:
Logging

Cause:

Action:

IAM-1011034
Error occurred while looking up plugin for : {0}

Category:
Logging

Cause:

Action:

IAM-1011035
Error occurred while adding admin-role : {0}

Category:
Logging

Cause:

Action:

IAM-1011036
Error occurred while adding admin-role membership for role: {0}

Category:
Logging

Cause:

Action:

IAM-1011037
Error occurred while removing admin-role membership with id: {0}

Category:
Logging

Cause:

Action:

IAM-1011038
Role membership not found for membership-id : {0}

Category:
Logging

Cause:

Action:

IAM-1011039
Unable to update role membership for membership-id : {0}

Category:
Logging

Cause:

Action:

IAM-1011040
Cannot persist a null AdminRoleMembership.

Category:
Logging

Cause:

Action:

IAM-1011041
Cannot assign a global scoped Admin Role :{0} to a non-top organization : {1}

Category:
Logging

Cause:

Action:

IAM-1011042
User {0} does not have permission for {1}

Category:
Logging

Cause:

Action:

IAM-1011043
User {0} does not have permission for {1} for scope : {2}

Category:
Logging

Cause:

Action:

IAM-1011044
The logged-in user {0} does not have {1} permission on {2} entity.

Category:
Logging

Cause:

Action:

IAM-1011045
Error occurred while granting role {0} to user {1}

Category:
Logging

Cause:

Action:

IAM-1011046
Error occurred while revoking role {0} to user {1}

Category:
Logging

Cause:

Action:

IAM-1011047
Error occurred while checking role grant.

Category:
Logging

Cause:

Action:

IAM-1011048
Error occurred while checking role grant for legacy role {0} for user-id {1}.

Category:
Logging

Cause:

Action:

IAM-1011049
Error while removing admin-role membership.

Category:
Logging

Cause:

Action:

IAM-1011050
Admin Role membership not found.

Category:
Logging

Cause:

Action:

IAM-1011051
Unable to update Admin Role membership.

Category:
Logging

Cause:

Action:

IAM-1011052
Unsupported operator {0}.

Category:
Logging

Cause:

Action:

IAM-1011053
Unsupported search criteria formed.

Category:
Logging

Cause:

Action:

IAM-1011054
Unable to retrieve the mapped capabilities from Authorization Policy Store.

Category:
Logging

Cause:

Action:

IAM-1011055
Users can not be assigned without the scope of control selected.

Category:
Logging

Cause:

Action:

IAM-1011056
Unable to create the authorization policy

Category:
Logging

Cause:

Action:

IAM-1011057
Unable to to modify the admin role, The admin role with the name does not exists.

Category:
Logging

Cause:

Action:

IAM-1011058
Unable to to create the admin role, The admin role with the name already exists.

Category:
Logging

Cause:

Action:

IAM-1011061
Unable to fetch the admin role owner and organization scoping.

Category:
Logging

Cause:

Action:

IAM-1011063
The selected resource {0} is not supported for fine grained admin-role creation.

Category:
Logging

Cause:

Action:

IAM-1011064
The specified admin-role name {0} contians non alphabet characters, Please specify only a-zA-Z characters.

Category:
Logging

Cause:

Action:

IAM-1011065
Admin Role can"t be created with {0} name.

Category:
Logging

Cause:

Action:

IAM-1011066
Cannot assign a global scoped Admin Role :{0} to non-top organizations.

Category:
Logging

Cause:

Action:

IAM-1020002
Task State change happening, {0} called

Category:
Logging

Cause:

Action:

IAM-1020003
Job Listener, Job execution vetoed {0}

Category:
Logging

Cause:

Action:

IAM-1020004
Job Listener, Job to be executed {0}

Category:
Logging

Cause:

Action:

IAM-1020005
Job Listener, Job was executed {0}

Category:
Logging

Cause:

Action:

IAM-1020006
Trigger state {0}

Category:
Logging

Cause:

Action:

IAM-1020007
Trigger Listener {0}

Category:
Logging

Cause:

Action:

IAM-1020008
Stop during {0}

Category:
Logging

Cause:

Action:

IAM-1020009
Interrupt called {0}

Category:
Logging

Cause:

Action:

IAM-1020010
StopTask call {0}

Category:
Logging

Cause:

Action:

IAM-1020011
Failed to stop a job.

Category:
Logging

Cause:

Action:

IAM-1020012
Scheduler State {0}

Category:
Logging

Cause:

Action:

IAM-1020013
Scheduled Task found {0}

Category:
Logging

Cause:

Action:

IAM-1020014
Method details {0}

Category:
Logging

Cause:

Action:

IAM-1020015
Plugin Store Exception for Listener {0}

Category:
Logging

Cause:

Action:

IAM-1020016
Plugin Exception for Listener {0}

Category:
Logging

Cause:

Action:

IAM-1020021
Exception encountered

Category:
Logging

Cause:

Action:

IAM-1020022
Class not found for entity {0}

Category:
Logging

Cause:

Action:

IAM-1020023
Method not implemented

Category:
Logging

Cause:

Action:

IAM-1020024
Execute default action handler with {0}

Category:
Logging

Cause:

Action:

IAM-1020025
Failed to execute handler

Category:
Logging

Cause:

Action:

IAM-1020026
Execute default entity previewer with {0}

Category:
Logging

Cause:

Action:

IAM-1020027
Scheduler exception encountered.

Category:
Logging

Cause:

Action:

IAM-1020029
Exception encountered in Scheduler execution {0}

Category:
Logging

Cause:

Action:

IAM-1020032
Scheduler Service {0}

Category:
Logging

Cause:

Action:

IAM-1020033
Failed to start Scheduler Service.

Category:
Logging

Cause:

Action:

IAM-1020034
Exception encountered in job execution {0}

Category:
Logging

Cause:

Action:

IAM-1020035
Error in exception object for job {0}

Category:
Logging

Cause:

Action:

IAM-1020036
Context exception encountered

Category:
Logging

Cause:

Action:

IAM-1020037
Job History not found for {0}

Category:
Logging

Cause:

Action:

IAM-1020038
Invalid parameter supplied for trigger expression.

Category:
Logging

Cause:

Action:

IAM-1020039
Invalid ScheduleTask definition

Category:
Logging

Cause:

Action:

IAM-1020040
The value is not set for required parameters of a schedule task.

Category:
Logging

Cause:

Action:

IAM-1020041
ScheduleTask is not set.

Category:
Logging

Cause:

Action:

IAM-1020042
Parameter value is not set properly.

Category:
Logging

Cause:

Action:

IAM-1020043
Error in getting ITResource implementation instance from plugin framework.

Category:
Logging

Cause:

Action:

IAM-1020045
Incorrect ScheduleTask definition

Category:
Logging

Cause:

Action:

IAM-1020046
More updated definition is present for Job {0}

Category:
Logging

Cause:

Action:

IAM-1020047
Last modify date is not set for {0}

Category:
Logging

Cause:

Action:

IAM-1020048
The user {0} does not have access for operation {1}

Category:
Logging

Cause:

Action:

IAM-1020050
Exception encountered during encryption of job parameter

Category:
Logging

Cause:

Action:

IAM-1020051
Exception encountered during decryption of job parameter

Category:
Logging

Cause:

Action:

IAM-1020052
The trigger name cannot be null.

Category:
Logging

Cause:

Action:

IAM-1020053
Exception encountered during creation of XML from velocity : {0}

Category:
Logging

Cause:

Action:

IAM-1020054
Data in XML for {0} attribute is not correct.

Category:
Logging

Cause:

Action:

IAM-1020055
Multiple ScheduleTasks configured for class {0}.

Category:
Logging

Cause:

Action:

IAM-1020056
Exception encountered while creating an XML document for ScheduleTask. Classname: {0}

Category:
Logging

Cause:

Action:

IAM-1020057
Exception encountered while saving ScheduleTask {0}

Category:
Logging

Cause:

Action:

IAM-1020058
Required attribute {0} is not set in the document.

Category:
Logging

Cause:

Action:

IAM-1020059
ScheduleTask with this name is already configured for class {0}. Please change the task name.

Category:
Logging

Cause:

Action:

IAM-1020060
Error calling {0} stored procedure : {1} {2}

Category:
Logging

Cause:

Action:

IAM-1020061
Running job {0} can not be deleted.

Category:
Logging

Cause:

Action:

IAM-1020062
Input parameters are incorrect {0} : {1}

Category:
Logging

Cause:

Action:

IAM-1020063
Incorrect format of Archival Date parameter. Archival Date is expected in DDMMYYYY or UI Date format.

Category:
Logging

Cause:

Action:

IAM-1020064
Job cannot be triggered because scheduler service is currently stopped.

Category:
Logging

Cause:

Action:

IAM-1020065
Job details cannot be null.

Category:
Logging

Cause:

Action:

IAM-1020066
No Such Job exists.

Category:
Logging

Cause:

Action:

IAM-1020067
Current Update Operation is not supported for Metadata Repository.

Category:
Logging

Cause:

Action:

IAM-1020068
Error occurred while reading or writing Metadata Repository.

Category:
Logging

Cause:

Action:

IAM-1020069
Conflicting updates made on Metadata Repository.

Category:
Logging

Cause:

Action:

IAM-1020070
Validation failure when validating Metadata Repository content.

Category:
Logging

Cause:

Action:

IAM-1020071
{0} file has been deleted from the Metadata Repository.

Category:
Logging

Cause:

Action:

IAM-1020072
Current Create Operation is not supported for Metadata Repository.

Category:
Logging

Cause:

Action:

IAM-1020073
Schedule task {0} already exists in Metadata Repository.

Category:
Logging

Cause:

Action:

IAM-1020074
Schedule task document is NULL.

Category:
Logging

Cause:

Action:

IAM-1020075
Invalid Reference.

Category:
Logging

Cause:

Action:

IAM-1020076
Invalid Namespace. Valid Namespace is {0}.

Category:
Logging

Cause:

Action:

IAM-1020077
Metadata already exists in Metadata Repository.

Category:
Logging

Cause:

Action:

IAM-1020078
Schedule task class {0} does not exists in classpath.

Category:
Logging

Cause:

Action:

IAM-1020079
Exception encountered while creating XML Document from Schedule Task Value Object.

Category:
Logging

Cause:

Action:

IAM-1020080
Invalid Trigger. End date {0} is before Start date {1}.

Category:
Logging

Cause:

Action:

IAM-1020081
Invalid Job Name. Job Name {0} is either NULL or empty.

Category:
Logging

Cause:

Action:

IAM-1020082
Invalid Job Name. Special characters are not allowed in Job Name {0}

Category:
Logging

Cause:

Action:

IAM-1020083
Exception encountered while updating XML Document from Schedule Task Value Object.

Category:
Logging

Cause:

Action:

IAM-1020084
Current Update Operation is not supported for Metadata Repository.

Category:
Logging

Cause:

Action:

IAM-1020085
Current Delete Operation is not supported for Metadata Repository.

Category:
Logging

Cause:

Action:

IAM-1020086
Task Name is NULL

Category:
Logging

Cause:

Action:

IAM-1020087
Unable to read Schedule Task definitions from plug-ins and corresponding error is {0}

Category:
Logging

Cause:

Action:

IAM-1020088
Job History for Job {0} can not be deleted.

Category:
Logging

Cause:

Action:

IAM-1020089
XML validation error and the error message is - {0}. Error on Column Number={1},Line Number={2}

Category:
Logging

Cause:

Action:

IAM-1020090
XML validation fatal error and the error message is - {0}. Error on Column Number={1},Line Number={2}

Category:
Logging

Cause:

Action:

IAM-1020091
XML validation warning - {0}. Warning on Column Number={1},Line Number={2}

Category:
Logging

Cause:

Action:

IAM-1020100
Constructor {0}

Category:
Logging

Cause:

Action:

IAM-1050000
Cannot register plugins from a directory. Expecting a zip file.

Category:
Logging

Cause:

Action:

IAM-1050001
plugin.xml is not found in the plugin zip {0}.

Category:
Logging

Cause:

Action:

IAM-1050002
Plugin {0} must implement the plugin point interface {1}

Category:
Logging

Cause:

Action:

IAM-1050003
The plugin zip does not contain the definition of plugin class {0}

Category:
Logging

Cause:

Action:

IAM-1050004
Plugin point {0} is not found in the class path.

Category:
Logging

Cause:

Action:

IAM-1050005
An error occurred while parsing the plugin.xml {0}

Category:
Logging

Cause:

Action:

IAM-1050006
An error occurred while loading the plugin class. Class {0} was not found.

Category:
Logging

Cause:

Action:

IAM-1050007
An error occurred while instantiating plugin: {0}

Category:
Logging

Cause:

Action:

IAM-1050008
An IO Error occurred while reading plugin bytes.

Category:
Logging

Cause:

Action:

IAM-1050009
An error occurred while storing the plugin in store {0}

Category:
Logging

Cause:

Action:

IAM-1050010
An error occurred while deleting plugin {0} from the plugin store.

Category:
Logging

Cause:

Action:

IAM-1050011
An error occurred while connecting to the database {0}

Category:
Logging

Cause:

Action:

IAM-1050012
An error occurred while retrieving the next value from the plugin sequence resultset

Category:
Logging

Cause:

Action:

IAM-1050013
An error occurred while rolling back changes to the database

Category:
Logging

Cause:

Action:

IAM-1050014
An error occurred while getting plugin {0} for plugin point {1}

Category:
Logging

Cause:

Action:

IAM-1050015
An error occurred while getting plugin {0} with version {1} for plugin point {2}

Category:
Logging

Cause:

Action:

IAM-1050016
An error occurred while getting versions of plugin {1}

Category:
Logging

Cause:

Action:

IAM-1050017
An error occurred while reading the plugin bytes with ID {0}

Category:
Logging

Cause:

Action:

IAM-1050018
An error occurred while getting the zip ID for plugin {0} with version {1} and plugin point {2}

Category:
Logging

Cause:

Action:

IAM-1050019
An error occurred while getting plugins for plugin point {0}

Category:
Logging

Cause:

Action:

IAM-1050020
No plugin exists with ID {0} in plugin store.

Category:
Logging

Cause:

Action:

IAM-1050021
An error occurred while initializing the plugin store.

Category:
Logging

Cause:

Action:

IAM-1050022
Unable to load plugins from {0}. Error {1}

Category:
Logging

Cause:

Action:

IAM-1050023
An error occurred while extracting plugins from plugin xml {0}

Category:
Logging

Cause:

Action:

IAM-1050024
The method is not supported for the plugin store {0}

Category:
Logging

Cause:

Action:

IAM-1050025
Plugin registration failed. Plugin zip file {0} was not found.

Category:
Logging

Cause:

Action:

IAM-1050026
XML schema validation error - Col={0}, Line={1} - {2}

Category:
Logging

Cause:

Action:

IAM-1050027
XML schema validation fatal error - Col={0}, Line={1} - {2}

Category:
Logging

Cause:

Action:

IAM-1050028
Failed to load XML schema, XML schema validation will be bypassed - {0}

Category:
Logging

Cause:

Action:

IAM-1050029
XML schema validation failed for {0} - {1}

Category:
Logging

Cause:

Action:

IAM-1050030
An error occurred while retrieving the next value from the plugin metadata sequence resultset.

Category:
Logging

Cause:

Action:

IAM-1051000
lib directory not found under {0}

Category:
Logging

Cause:

Action:

IAM-1052000
Filewatcher thread started with delay {0}

Category:
Logging

Cause:

Action:

IAM-1052001
Registered plugin directory {0} is not found on the file system. Ignoring.

Category:
Logging

Cause:

Action:

IAM-1052002
Format of file {0} is not known. This should be a zip file or a directory. Ignoring.

Category:
Logging

Cause:

Action:

IAM-1052003
Directory {0} is deleted from file system.

Category:
Logging

Cause:

Action:

IAM-1052004
FileWatcher thread configuration is inactive. No plugins will be loaded dynamically from file system.

Category:
Logging

Cause:

Action:

IAM-1052005
Deregistered the plugin with ID {0}. The plugin information is removed from the local cache.

Category:
Logging

Cause:

Action:

IAM-1052006
The plugin class loader with zip id {0} is invalidated on some other node. Invalidating the plugin class loader in this node.

Category:
Logging

Cause:

Action:

IAM-1052007
Performing XML schema validation on {0}

Category:
Logging

Cause:

Action:

IAM-1052008
Plugins are loaded from new directory {0}

Category:
Logging

Cause:

Action:

IAM-1052009
Plugins are loaded from new zip file {0}

Category:
Logging

Cause:

Action:

IAM-1052010
Reloading interval should not be less than 15 seconds, setting it to 15 seconds

Category:
Logging

Cause:

Action:

IAM-1054000
Plugin {0} doesn"t implement plugin point interface {1}. Ignoring the in-built pluign.

Category:
Logging

Cause:

Action:

IAM-1054001
Plugin point {0} is not found in class path. Ignoring the in-built plugin {1}.

Category:
Logging

Cause:

Action:

IAM-1054002
Plugin {0} is not found in class path. Ignoring the in-built plugin with plugin point id {1}.

Category:
Logging

Cause:

Action:

IAM-1054003
An error occurred while loading the plugin instance metadata. {0}

Category:
Logging

Cause:

Action:

IAM-1054004
An error occurred while parsing the plugin instance metadata. {0}

Category:
Logging

Cause:

Action:

IAM-1054005
An error occurred while loading the plugin point metadata. {0}

Category:
Logging

Cause:

Action:

IAM-1054006
An error occurred while parsing the plugin point metadata. {0}

Category:
Logging

Cause:

Action:

IAM-1054007
An error occurred while resolving runtime value {0} for plugin point {1}. {2}

Category:
Logging

Cause:

Action:

IAM-1054008
Incompatible data type - {0} returned by runtime value resolver for plugin point {1}.

Category:
Logging

Cause:

Action:

IAM-1054009
An error occurred while registering MDS listener. {0}

Category:
Logging

Cause:

Action:

IAM-1054010
XML schema validation warning - Col={0}, Line={1} - {2}

Category:
Logging

Cause:

Action:

IAM-1054011
An error reading reloading interval from configuration, reloading interval is set to {0} seconds

Category:
Logging

Cause:

Action:

IAM-1060001
The system property with key {0} already exists.

Category:
Logging

Cause:

Action:

IAM-1060002
The system property with key {0} cannot be updated.

Category:
Logging

Cause:

Action:

IAM-1060003
The system property with keyword {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-1060004
The state of system property with key {0} was not updated.

Category:
Logging

Cause:

Action:

IAM-1060005
The system property with key {0} cannot be deleted.

Category:
Logging

Cause:

Action:

IAM-1060006
The user {0} does not have access for operation {1}

Category:
Logging

Cause:

Action:

IAM-1060007
The value {0} cannot be assigned to {1} property. Please check the values allowed for this key.

Category:
Logging

Cause:

Action:

IAM-1060008
Execute default action handler with {0}

Category:
Logging

Cause:

Action:

IAM-1060009
An error occurred while executing action handler with process id : {0}. event id : {1}

Category:
Logging

Cause:

Action:

IAM-1060010
Missing value for {0}

Category:
Logging

Cause:

Action:

IAM-1060011
Keyword {0} is already used by another system property. Please use another keyword.

Category:
Logging

Cause:

Action:

IAM-1070000
The logged user {0} does not have permission to register the plug in.

Category:
Logging

Cause:

Action:

IAM-1070001
The logged user {0} does not have permission to unregister the plug in.

Category:
Logging

Cause:

Action:

IAM-1070002
Exception occurred {0}

Category:
Logging

Cause:

Action:

IAM-1070004
The input stream to read contents is {0}

Category:
Logging

Cause:

Action:

IAM-1070005
The jar file does not exist at the location {0}

Category:
Logging

Cause:

Action:

IAM-1070006
Caught SQLIntegrityViolationException for {0}

Category:
Logging

Cause:

Action:

IAM-1070007
The jar file {0} updated successfully.

Category:
Logging

Cause:

Action:

IAM-1070008
The jar file {0} cannot be updated.

Category:
Logging

Cause:

Action:

IAM-1070009
Invalid response

Category:
Logging

Cause:

Action:

IAM-1070011
Exception found {0}.Rolling back the transaction.

Category:
Logging

Cause:

Action:

IAM-1070012
The jar file {0} inserted successfully.

Category:
Logging

Cause:

Action:

IAM-1070015
The set of JarElements is empty

Category:
Logging

Cause:

Action:

IAM-1070016
The jar file location cannot be empty. Exiting.

Category:
Logging

Cause:

Action:

IAM-1070017
The Jar Type cannot be null.Exiting.

Category:
Logging

Cause:

Action:

IAM-1070018
Invalid Type number.Please enter a valid type

Category:
Logging

Cause:

Action:

IAM-1070019
Resource Bundle {0} inserted successfully.

Category:
Logging

Cause:

Action:

IAM-1070021
Resource Bundle does not exist at the location {0}

Category:
Logging

Cause:

Action:

IAM-1070022
Resource Bundle {0} updated successfully

Category:
Logging

Cause:

Action:

IAM-1070023
Resource Bundle {0} cannot be updated.

Category:
Logging

Cause:

Action:

IAM-1070024
Incorrect usage of the utility

Category:
Logging

Cause:

Action:

IAM-1070025
The cache category name {0} is invalid.

Category:
Logging

Cause:

Action:

IAM-1070032
The jar file {0} is deleted successfully.

Category:
Logging

Cause:

Action:

IAM-1070033
The jar name cannot be empty. Exiting.

Category:
Logging

Cause:

Action:

IAM-1070034
The given directory does not exist {0}

Category:
Logging

Cause:

Action:

IAM-1070035
The file {0} downloaded successfully at given location.

Category:
Logging

Cause:

Action:

IAM-1070036
The set of ResourceElements is empty

Category:
Logging

Cause:

Action:

IAM-1070037
The Resource Type cannot be null.Exiting.

Category:
Logging

Cause:

Action:

IAM-1070038
The resource file location cannot be empty. Exiting.

Category:
Logging

Cause:

Action:

IAM-1070039
The path of download directory name cannot be empty. Exiting.

Category:
Logging

Cause:

Action:

IAM-1070040
The resource bundle file {0} is deleted successfully.

Category:
Logging

Cause:

Action:

IAM-1070041
The resource bundle file name cannot be empty. Exiting.

Category:
Logging

Cause:

Action:

IAM-1070042
The logged user {0} does not have permission to complete the async handler

Category:
Logging

Cause:

Action:

IAM-1070043
Now trying with updating of the Jar {0}

Category:
Logging

Cause:

Action:

IAM-1070044
The jar file: {0} does not exist in the database.

Category:
Logging

Cause:

Action:

IAM-1070045
The properties file: {0} does not exist in the database.

Category:
Logging

Cause:

Action:

IAM-1070046
An error occurred while uploading jars.

Category:
Logging

Cause:

Action:

IAM-1070047
An error occurred while updating jars.

Category:
Logging

Cause:

Action:

IAM-1070048
An error occurred while loading a jar to database.

Category:
Logging

Cause:

Action:

IAM-1070049
An error occurred while downloading jars.

Category:
Logging

Cause:

Action:

IAM-1070050
An error occurred while downloading a jar from database.

Category:
Logging

Cause:

Action:

IAM-1070051
An error occurred while deleting jars.

Category:
Logging

Cause:

Action:

IAM-1070052
An error occurred while uploading resource bundles.

Category:
Logging

Cause:

Action:

IAM-1070053
An error occurred while downloading resource bundles.

Category:
Logging

Cause:

Action:

IAM-1070054
An error occurred while trying to close file.

Category:
Logging

Cause:

Action:

IAM-1070055
An error occurred while deleting resource bundles.

Category:
Logging

Cause:

Action:

IAM-1070056
An error occurred while processing lookup query

Category:
Logging

Cause:

Action:

IAM-1070057
Unable to fetch the users assigned with the admin-role.

Category:
Logging

Cause:

Action:

IAM-1070058
Unable to fetch the owner detail.

Category:
Logging

Cause:

Action:

IAM-1070059
Unable to fetch the admin role organization scope.

Category:
Logging

Cause:

Action:

IAM-1070060
Unable to search the users.

Category:
Logging

Cause:

Action:

IAM-1070061
Please check if the Workflow Policies Enabled

Category:
Logging

Cause:

Action:

IAM-1070062
Error while getting the system property

Category:
Logging

Cause:

Action:

IAM-1080004
Cannot find the template.

Category:
Logging

Cause:

Action:

IAM-1080005
Cannot load the Resolver class {0}.

Category:
Logging

Cause:

Action:

IAM-1080006
Cannot find Event Variable {0}.

Category:
Logging

Cause:

Action:

IAM-1080007
Look-up failed for {1}.

Category:
Logging

Cause:

Action:

IAM-1080008
Cannot fetch 91 entity with name {0}.

Category:
Logging

Cause:

Action:

IAM-1080010
Cannot find an event handler for {0} stage.

Category:
Logging

Cause:

Action:

IAM-1080013
Cannot load event from configuration - {0}.

Category:
Logging

Cause:

Action:

IAM-1080014
Authorization check failed for {0} Operation for user {1}.

Category:
Logging

Cause:

Action:

IAM-1080021
Last modify date is not set.

Category:
Logging

Cause:

Action:

IAM-1080022
{0} was already updated by another user.

Category:
Logging

Cause:

Action:

IAM-1080023
An exception occurred while creating the notification template.

Category:
Logging

Cause:

Action:

IAM-1080025
An exception occurred while modifying the notification template.

Category:
Logging

Cause:

Action:

IAM-1080026
Template already exists.

Category:
Logging

Cause:

Action:

IAM-1080027
Cannot load plugin for reading mail server configuration.

Category:
Logging

Cause:

Action:

IAM-1080028
Cannot find details for user {0}.

Category:
Logging

Cause:

Action:

IAM-1080030
An exception occurred while resolving the user data.

Category:
Logging

Cause:

Action:

IAM-1080031
Cannot retrieve the system default locale.

Category:
Logging

Cause:

Action:

IAM-1080032
Cannot find the email ID or the locale for this user {0}.

Category:
Logging

Cause:

Action:

IAM-1080033
An unknown error occurred while sending the notification.

Category:
Logging

Cause:

Action:

IAM-1080034
Cannot load the email service provider.

Category:
Logging

Cause:

Action:

IAM-1080035
Notification Event {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-1080036
OIM Default Notification Template {0} cannot be deleted.

Category:
Logging

Cause:

Action:

IAM-1080037
IT Resource {0} is not present.

Category:
Logging

Cause:

Action:

IAM-1080038
No users specified for this Event

Category:
Logging

Cause:

Action:

IAM-1080039
NotificationEvent object cannot be null.

Category:
Logging

Cause:

Action:

IAM-1080040
UMS Webservice URL is either NULL or Empty.

Category:
Logging

Cause:

Action:

IAM-1080041
UMS Webservice URL is invalid. Exact error: {0}

Category:
Logging

Cause:

Action:

IAM-1080043
An error occurred while resolving the template data with generic resolver in {0} method.

Category:
Logging

Cause:

Action:

IAM-1080044
Cannot find User details for user Email {0}.

Category:
Logging

Cause:

Action:

IAM-1080060
Cannot retrieve the system property {0} for disabling of notifications.

Category:
Logging

Cause:

Action:

IAM-1080061
Notifications are disabled at system level.

Category:
Logging

Cause:

Action:

IAM-1080062
Template {0} is disabled.

Category:
Logging

Cause:

Action:

IAM-1080063
An error occurred while reading plugins from the Plugins Registry : {0}

Category:
Logging

Cause:

Action:

IAM-1080064
An error occurred while reading Notification Event definition for the plugin with the details : {0} and the error is {1}

Category:
Logging

Cause:

Action:

IAM-1080065
An error occurred while reading XML document for the plugin with the details : {0} and the error is {1}

Category:
Logging

Cause:

Action:

IAM-1080066
Event Name cannot be NULL or empty for {0} template operation.

Category:
Logging

Cause:

Action:

IAM-1080067
Notification Template Name cannot be NULL or empty for {0} template operation.

Category:
Logging

Cause:

Action:

IAM-1080068
Content Encoding for Template cannot be NULL or empty for {0} template operation.

Category:
Logging

Cause:

Action:

IAM-1080069
Message Subject for Template cannot be NULL or empty for {0} template operation.

Category:
Logging

Cause:

Action:

IAM-1080070
Content Type for Template cannot be NULL or empty for {0} template operation.

Category:
Logging

Cause:

Action:

IAM-1080071
Long Message for Template cannot be NULL or empty for {0} template operation.

Category:
Logging

Cause:

Action:

IAM-1080072
UMS Email Service Provider cannot be configured to send mails when Workflows are disabled.

Category:
Logging

Cause:

Action:

IAM-1080073
SOA Email Service Provider cannot be configured to send mails when Workflows are disabled.

Category:
Logging

Cause:

Action:

IAM-1080074
XML validation error and the error message is - {0}. Error on Column Number={1},Line Number={2}

Category:
Logging

Cause:

Action:

IAM-1080075
XML validation fatal error and the error message is - {0}. Error on Column Number={1},Line Number={2}

Category:
Logging

Cause:

Action:

IAM-1080076
XML validation warning - {0}. Warning on Column Number={1},Line Number={2}

Category:
Logging

Cause:

Action:

IAM-1080077
Notification template for {0} locale is not found.

Category:
Logging

Cause:

Action:

IAM-1081017
Cannot find resolver for {0}.

Category:
Logging

Cause:

Action:

IAM-1081018
An error occurred while resolving the template data.

Category:
Logging

Cause:

Action:

IAM-1081019
Cannot find MetaData.

Category:
Logging

Cause:

Action:

IAM-1081020
Messaging exception thrown from email provider.

Category:
Logging

Cause:

Action:

IAM-1090001
Authorization advice invoked with invalid parameter count {0}.

Category:
Logging

Cause:

Action:

IAM-1090002
Authorization advice invoked with invalid parameter type, expected {0} received {1}.

Category:
Logging

Cause:

Action:

IAM-1090003
Authorization advice invoked with object that has a empty policy type id.

Category:
Logging

Cause:

Action:

IAM-1090004
Authorization advice could not retrieve policy type for policy type id {0}.

Category:
Logging

Cause:

Action:

IAM-1090005
Authorization advice could not retrieve policy for policy id {0}.

Category:
Logging

Cause:

Action:

IAM-1090006
Access denied because user with id {0} doesn"t have authorization.

Category:
Logging

Cause:

Action:

IAM-1090007
Authorization advice invoked with invalid empty parameter {0}.

Category:
Logging

Cause:

Action:

IAM-1090008
Authorization advice invoked with invalid target class {0}.

Category:
Logging

Cause:

Action:

IAM-1090010
Authorization advice for target class {0} invoked with unknown method name {1}.

Category:
Logging

Cause:

Action:

IAM-1090011
Policy type not found.

Category:
Logging

Cause:

Action:

IAM-1090012
Action not allowed for policy type {0} and method {1}.

Category:
Logging

Cause:

Action:

IAM-1090200
Data type validation failed for {0}.

Category:
Logging

Cause:

Action:

IAM-1090201
Data type validation failed because data type is null.

Category:
Logging

Cause:

Action:

IAM-1090203
Invalid list data type for condition {0}.

Category:
Logging

Cause:

Action:

IAM-1090205
Invalid data types {0} and {1} for condition {2}.

Category:
Logging

Cause:

Action:

IAM-1090207
Invalid arg "{0}" does not begin with a path element that this policy type supports.

Category:
Logging

Cause:

Action:

IAM-1090300
Delete rule not allowed due to dependency on audit violations, entity ID {0}.

Category:
Logging

Cause:

Action:

IAM-1090301
Could not delete rule due to rule entity dependencies, entity ID {0}.

Category:
Logging

Cause:

Action:

IAM-1090305
Delete policy not allowed due to dependency on audit violations, entity ID {0}.

Category:
Logging

Cause:

Action:

IAM-1090306
Could not delete policy due to rule entity dependencies, entity ID {0}.

Category:
Logging

Cause:

Action:

IAM-1090400
Policy type with policy type identifier {0} not found for the following reason: {1}.

Category:
Logging

Cause:

Action:

IAM-1090401
Following exception received: {0}.

Category:
Logging

Cause:

Action:

IAM-1090402
Failed to load policy type schema with class path of {0} for the following reason: {1}.

Category:
Logging

Cause:

Action:

IAM-1090403
Path element list is empty.

Category:
Logging

Cause:

Action:

IAM-1090404
Path element search did not find a non-value path element in the path element list.

Category:
Logging

Cause:

Action:

IAM-1090405
Allowed top path element with name {0} not found in policy type with name {1}.

Category:
Logging

Cause:

Action:

IAM-1090406
Invalid operation {0} for policy type with name {1}.

Category:
Logging

Cause:

Action:

IAM-1090407
Evaluation for policy with name {0} failed because the policy is disabled.

Category:
Logging

Cause:

Action:

IAM-1090408
Policy type seeding failed with the following exception: {0}.

Category:
Logging

Cause:

Action:

IAM-1090409
Rule with rule id {0} returned a null policy relation.

Category:
Logging

Cause:

Action:

IAM-1090410
ReturnValue must specify either an attribute value or groovy expression.

Category:
Logging

Cause:

Action:

IAM-1090411
No return values specified for policy type requiring return value.

Category:
Logging

Cause:

Action:

IAM-1090413
Generic listener initialize failed with the following exception: {0}.

Category:
Logging

Cause:

Action:

IAM-1090414
Error loading user for user id {0}.

Category:
Logging

Cause:

Action:

IAM-1090415
Error loading rule for rule id {0}.

Category:
Logging

Cause:

Action:

IAM-1090417
Replace rules for policy id {0} failed for the following reason: {1}.

Category:
Logging

Cause:

Action:

IAM-2010001
Cancellation of workflow failed with the exception {0}

Category:
Logging

Cause:

Action:

IAM-2010002
Unable to instantiate the workflow process due to: {0}

Category:
Logging

Cause:

Action:

IAM-2010003
Unable to get the state of the bpel process due to {0}

Category:
Logging

Cause:

Action:

IAM-2010004
Unable to get the status of the bpel process due to {0}

Category:
Logging

Cause:

Action:

IAM-2010006
There are no valid definitions with the definition name {0}

Category:
Logging

Cause:

Action:

IAM-2010008
Registration of the workflow definition failed as the category {0} specified in the workflow definition with name {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-2010010
Error reading the category xml documents

Category:
Logging

Cause:

Action:

IAM-2010012
There is no category with the name {0}

Category:
Logging

Cause:

Action:

IAM-2010013
There is no instance with the instanceID {0}

Category:
Logging

Cause:

Action:

IAM-2010014
Error in instantiating the callbackclass {0} with exception {1}

Category:
Logging

Cause:

Action:

IAM-2010015
Error in accessing the callbackclass {0} with exception {1}

Category:
Logging

Cause:

Action:

IAM-2010016
Error in finding the callbackclass {0} with exception {1}

Category:
Logging

Cause:

Action:

IAM-2010017
The callback webservice is called with instanceid: {0} and outcome {1}

Category:
Logging

Cause:

Action:

IAM-2010018
The workflow definition for instance {0} is {1}

Category:
Logging

Cause:

Action:

IAM-2010019
The category for workflow definition {0} is {1}

Category:
Logging

Cause:

Action:

IAM-2010020
The callbackclass for category {0} is {1}

Category:
Logging

Cause:

Action:

IAM-2010022
BPEL process {0} has been initiated successfully

Category:
Logging

Cause:

Action:

IAM-2010023
Tasklist mapping failed for workflow definition: {0} due to {1}

Category:
Logging

Cause:

Action:

IAM-2010024
Registration failed as the input property {0} is not present

Category:
Logging

Cause:

Action:

IAM-2010025
Incorrect username/password entered during registration of workflow

Category:
Logging

Cause:

Action:

IAM-2010026
Not able to load the input property file {0}. Make sure the location is correct

Category:
Logging

Cause:

Action:

IAM-2010027
Error during registration of workflow definition {0}

Category:
Logging

Cause:

Action:

IAM-2010030
The operation {0} on instanceid {1} failed since the definition is not enabled

Category:
Logging

Cause:

Action:

IAM-2010031
The workflow definition with name {0} already exists in OIM.

Category:
Logging

Cause:

Action:

IAM-2010032
List of registered workflow definition

Category:
Logging

Cause:

Action:

IAM-2010033
This tool helps in doing the following operations register -------- Registers a given workflow in OIM DB. This tool also does the flex field mappings for tasks fields. Input: i) oim admin credentials ii) oim managed server URL iii) Domain of the workflow iv) Name of the workflow v) Version of the workflow vi) Service name of the workflow vii) Human tasks in the workflow (multiple human tasks must be separated by colon(:)) disable ------- Disables a given workflow composites from OIM. Once workflow composites are disabled, no operations can be done on

the workflow. Input: i) oim admin credentials ii) domain name(default is "default") iii) workflow name iv) version of the deployed composite enable ------ Enables a workflow already registered with OIM Also does flex field mapping for the task fields Input : i) oim admin credentials ii) domain name(default is "default") iii) workflow name iv) version of the deployed composite

Category:
Logging

Cause:

Action:

IAM-2010034
The task {0} specified for the workflow composite {1} is not valid

Category:
Logging

Cause:

Action:

IAM-2010035
Cant enable the composite {0} which is already enabled

Category:
Logging

Cause:

Action:

IAM-2010036
Cant disable the composite {0} which is already disabled

Category:
Logging

Cause:

Action:

IAM-2010037
Skipping the task mapping as no human tasks are associated with the composite {0}

Category:
Logging

Cause:

Action:

IAM-2010038
Withdrawal of workflow failed with the exception {0}

Category:
Logging

Cause:

Action:

IAM-2010039
Workflow DN is passed as null

Category:
Logging

Cause:

Action:

IAM-2010040
Workflow DN {0} is invalid

Category:
Logging

Cause:

Action:

IAM-2010041
Error occurred while searching SOA composites in SOA server

Category:
Logging

Cause:

Action:

IAM-2010043
The composite {0} does not exist on SOA server

Category:
Logging

Cause:

Action:

IAM-2010044
Registration of workflow {0} failed. Following values were passed for registering the workflow: \n(1)Category={1} \n(2)OperationId={2} \n(3)PayloadID={3} \n(4)ProviderType={4} \n(5)Service Name={5} \n(6)ListOfTasks={6}.

Category:
Logging

Cause:

Action:

IAM-2010045
Error occurred while updating human task uri information for composite {0}.

Category:
Logging

Cause:

Action:

IAM-2010046
Skipping the task uri update as no human tasks are associated with the composite {0}

Category:
Logging

Cause:

Action:

IAM-2010047
An error occurred in {0} while withdrawing tasks for composite with name {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-2010048
An error occurred in {0} while withdrawing tasks for composite with name {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-2010049
An error occurred while creating view {0}.

Category:
Logging

Cause:

Action:

IAM-2010050
Skipping the view update as no human tasks are associated with the composite {0}

Category:
Logging

Cause:

Action:

IAM-2010051
View - {0} does not exist, so creating new view.

Category:
Logging

Cause:

Action:

IAM-2010052
Error occurred while updating view for composite {0}.

Category:
Logging

Cause:

Action:

IAM-2010053
Updating view {0}.

Category:
Logging

Cause:

Action:

IAM-2010054
OIM front-end url {0} doesn''t follow supported format. It should be of the format http(s)://host(:port)

Category:
Logging

Cause:

Action:

IAM-2020001
Error in calling xellerate API for IT Resource.

Category:
Logging

Cause:

Action:

IAM-2020002
IT Resource is not found for lookup criteria

Category:
Logging

Cause:

Action:

IAM-2020003
Method details {0}

Category:
Logging

Cause:

Action:

IAM-2030000
[CALLBACKMSG] Error while creating callback record for orchestration process {0}, event {1} and callback {2}. Exception is {3}.

Category:
Logging

Cause:

Action:

IAM-2030002
[CALLBACKMSG] Error occurred while storing result of callback invocation for correlation id {0}.

Category:
Logging

Cause:

Action:

IAM-2030003
[CALLBACKMSG] Exception when adding result for callback record, error is {0}.

Category:
Logging

Cause:

Action:

IAM-2030004
[CALLBACKMSG] Error while searching callback records for orchestration process {0} and event {1}. Exception is {2}.

Category:
Logging

Cause:

Action:

IAM-2030017
[CALLBACKMSG] Exception in getting previous invocation records in db for orchestration {0}, event {1} in response processing. Message is {2}. Cannot proceed. Orchestration will remain in pending state as a result.

Category:
Logging

Cause:

Action:

IAM-2030018
[CALLBACKMSG] Orchestration event not in pending state in post process response handle for process id {0}, event id {1}. Will not change orchestration status.

Category:
Logging

Cause:

Action:

IAM-2030019
[CALLBACKMSG] Successfully completed async post process handler for process id {0}, event id {1}. Moving kernel orchestration to next state.

Category:
Logging

Cause:

Action:

IAM-2030021
[CALLBACKMSG] Exception in updating result of invocation record in db for orchestration {0}, event {1} in response processing. Message is {2}.

Category:
Logging

Cause:

Action:

IAM-2030037
[CALLBACKMSG] Callback configuration schema file {0} not found.

Category:
Logging

Cause:

Action:

IAM-2030038
[CALLBACKMSG] Invalid input to getCallbacksToInvoke, step type {0}, entity {1}, operation {2}, eventData {3}.

Category:
Logging

Cause:

Action:

IAM-2030086
[CALLBACKMSG] For entity {0}, operation {1}, step {2}, applicable policies are {3}.

Category:
Logging

Cause:

Action:

IAM-2030087
[CALLBACKMSG] Match for policy name {0} is {1}.

Category:
Logging

Cause:

Action:

IAM-2030088
[CALLBACKMSG] Null callback name while creating callback invocation record. Can not proceed.

Category:
Logging

Cause:

Action:

IAM-2030090
[CALLBACKMSG] Found {0} possible matches for applicable policies for step {1}, entity {2}, operation {3}.

Category:
Logging

Cause:

Action:

IAM-2030094
[CALLBACKMSG] Null or invalid policy state while matching policy {0}. Will evaluate to false.

Category:
Logging

Cause:

Action:

IAM-2030115
[CALLBACKMSG] Loaded callback configuration for mds reference {0}.

Category:
Logging

Cause:

Action:

IAM-2030126
[CALLBACKMSG] Multiple or zero entities found for guid {0}, not using any in callback message.

Category:
Logging

Cause:

Action:

IAM-2030127
[CALLBACKMSG] Exception when searching entities with guid {0}. Exception is {1}.

Category:
Logging

Cause:

Action:

IAM-2030142
[CALLBACKMSG] Updated SoD callback FAILURE error code for process id {0}, event id {1}

Category:
Logging

Cause:

Action:

IAM-2030143
[CALLBACKMSG] Exception in updating SoD Callback FAILURE result for orchestration {0}, event {1} . Message is {2}.

Category:
Logging

Cause:

Action:

IAM-2030151
[CALLBACKMSG] Unable to fetch callback record with the correlation id {0}

Category:
Logging

Cause:

Action:

IAM-2030162
[CALLBACKMSG] Tenant GUID not present in request or orchestration data.

Category:
Logging

Cause:

Action:

IAM-2030163
[CALLBACKMSG] Exception occurred while getting entity information to find tenant GUID.

Category:
Logging

Cause:

Action:

IAM-2030164
[CALLBACKMSG] No callback policies are configured. Request will not be processed further for callbacks.

Category:
Logging

Cause:

Action:

IAM-2030400
[CALLBACKMSG] Error occurred while creating {0} record in DB. Error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2030401
[CALLBACKMSG] Error occurred while creating {0} record with {1} {2} in DB. Error message is {3}.

Category:
Logging

Cause:

Action:

IAM-2030402
[CALLBACKMSG] Error occurred while deleting {0} record with {1} {2} from DB. Error message is {3}.

Category:
Logging

Cause:

Action:

IAM-2030403
[CALLBACKMSG] Error occurred while retrieving {0} record with {1} {2} from DB. Error message is {3}.

Category:
Logging

Cause:

Action:

IAM-2030404
[CALLBACKMSG] Data validation failed. Parameter {0} passed is null or invalid.

Category:
Logging

Cause:

Action:

IAM-2040001
Execute enable provisioned resource action handler with {0}

Category:
Logging

Cause:

Action:

IAM-2040002
Error occurred while finding beneficiaries

Category:
Logging

Cause:

Action:

IAM-2040003
Error occurred while obtaining instance key

Category:
Logging

Cause:

Action:

IAM-2040004
Enabling the instance {0}

Category:
Logging

Cause:

Action:

IAM-2040005
Error occurred while executing action handler

Category:
Logging

Cause:

Action:

IAM-2040006
Execute disable provisioned resource action handler with Process id {0} and Event id {1}

Category:
Logging

Cause:

Action:

IAM-2040007
Disabling the instance {0}

Category:
Logging

Cause:

Action:

IAM-2040008
Execute deprovision provisioned resource action handler with {0}

Category:
Logging

Cause:

Action:

IAM-2040009
Deprovisioning the instance {0}

Category:
Logging

Cause:

Action:

IAM-2040010
Execute modify provisioned resource action handler with {0}

Category:
Logging

Cause:

Action:

IAM-2040013
Execute provision resource action handler with {0}

Category:
Logging

Cause:

Action:

IAM-2040014
Error occurred while finding SDK_KEY corresponding to process instance key {0}

Category:
Logging

Cause:

Action:

IAM-2040015
Error occurred while finding form related details corresponding to SDK_KEY {0}

Category:
Logging

Cause:

Action:

IAM-2040016
Error occurred while setting data for form " {0} "

Category:
Logging

Cause:

Action:

IAM-2040021
Error while finding request model for the request

Category:
Logging

Cause:

Action:

IAM-2040022
Error while finding process instance key for oiuKey {0}

Category:
Logging

Cause:

Action:

IAM-2040023
Error while finding version for sdk key {0}

Category:
Logging

Cause:

Action:

IAM-2040024
Error while finding field and labels for form " {0} "

Category:
Logging

Cause:

Action:

IAM-2040025
Error while finding child form related details

Category:
Logging

Cause:

Action:

IAM-2040026
Error occurred while provisioning resource with key {0} to user {1}

Category:
Logging

Cause:

Action:

IAM-2040027
An error occurred while finding the user for corresponding {0} "{1}"

Category:
Logging

Cause:

Action:

IAM-2040028
User does not exists

Category:
Logging

Cause:

Action:

IAM-2040030
User {0} is already {1}.

Category:
Logging

Cause:

Action:

IAM-2040031
Error occurred while finding roles assigned to user for corresponding {0} "{1}".

Category:
Logging

Cause:

Action:

IAM-2040032
{0} {1} is already assigned to or pending for user having {2} "{3}"

Category:
Logging

Cause:

Action:

IAM-2040033
{0} {1} is neither assigned to nor pending for user having {2} "{3}"

Category:
Logging

Cause:

Action:

IAM-2040035
{0} {1} has already been reserved. Please provide another {2}

Category:
Logging

Cause:

Action:

IAM-2040036
An error occurred while searching for the lookup values defined for lookup-code {0}

Category:
Logging

Cause:

Action:

IAM-2040037
An error occurred while getting IT Resource Instances defined for IT Resource Type {0}

Category:
Logging

Cause:

Action:

IAM-2040042
{0} {1} are already assigned to user for corresponding {2} "{3}"

Category:
Logging

Cause:

Action:

IAM-2040043
{0} {1} are not assigned to user for corresponding {2} "{3}"

Category:
Logging

Cause:

Action:

IAM-2040045
User with value "{1}" for attribute {0} already exists. Please choose another value for attribute {0}

Category:
Logging

Cause:

Action:

IAM-2040046
The value {1} for attribute {0} is not valid. Please enter valid value for attribute {0}.

Category:
Logging

Cause:

Action:

IAM-2040048
Error occurred while getting resource name. Underlying error messages is {0}

Category:
Logging

Cause:

Action:

IAM-2040049
UserManager Access Denied.

Category:
Logging

Cause:

Action:

IAM-2040050
Organization Search Failed.

Category:
Logging

Cause:

Action:

IAM-2040054
The specified column is not defined in the result set.

Category:
Logging

Cause:

Action:

IAM-2040055
An error occurred while getting unassigned roles for the user.

Category:
Logging

Cause:

Action:

IAM-2040056
An error occurred while getting assigned roles for the user.

Category:
Logging

Cause:

Action:

IAM-2040057
An error occurred while getting entities.

Category:
Logging

Cause:

Action:

IAM-2040058
The specified resource does not exist.

Category:
Logging

Cause:

Action:

IAM-2040059
An error occurred while getting corresponding users for the entity.

Category:
Logging

Cause:

Action:

IAM-2040060
An error occurred while getting available objects.

Category:
Logging

Cause:

Action:

IAM-2040062
An error occurred while getting form details. The form does not exist.

Category:
Logging

Cause:

Action:

IAM-2040063
An error occurred while getting form details.

Category:
Logging

Cause:

Action:

IAM-2040064
Not an Atomic Operation.

Category:
Logging

Cause:

Action:

IAM-2040065
The Form version does not exist.

Category:
Logging

Cause:

Action:

IAM-2040066
The resource specified is not provisioned for the given user.

Category:
Logging

Cause:

Action:

IAM-2040067
Role(s) cannot be assigned/revoked to disabled/deleted users.

Category:
Logging

Cause:

Action:

IAM-2040069
An error has occurred while searching for users.

Category:
Logging

Cause:

Action:

IAM-2040070
Error occurred while finding resource objects. Underlying error messages is {0}

Category:
Logging

Cause:

Action:

IAM-2040076
The {0} with value {1} already exists under the container {2} or is reserved.

Category:
Logging

Cause:

Action:

IAM-2040084
Can not modify role grant.

Category:
Logging

Cause:

Action:

IAM-2040450
Error in role creation as Role {0} exists.

Category:
Logging

Cause:

Action:

IAM-2040451
Invalid rolekey(s) {0} passed for Modify role operation.

Category:
Logging

Cause:

Action:

IAM-2040452
Invalid rolekey(s) {0} passed for Delete role operation.

Category:
Logging

Cause:

Action:

IAM-2040453
Dynamic Role cannot have Static members in LDAP Mode

Category:
Logging

Cause:

Action:

IAM-2040501
Error occurred while generating additional payload details. Exception is {0}

Category:
Logging

Cause:

Action:

IAM-2040502
Error getting request details : {0}

Category:
Logging

Cause:

Action:

IAM-2040503
Request Id is null. Cannot proceed.

Category:
Logging

Cause:

Action:

IAM-2040505
Ignoring the deletion of child data which does not exist while fulfilling request : {0}

Category:
Logging

Cause:

Action:

IAM-2040600
An error occurred while getting dependent resource details. The underlying error message is: {0}

Category:
Logging

Cause:

Action:

IAM-2040601
An error while retrieving user attribute definitions. The underlying error message is: {0}

Category:
Logging

Cause:

Action:

IAM-2040602
An error occurred while searching for application instances given account key(s) {0}. Underlying error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2040603
An error occurred while searching for entitlements given entitlement instance key(s) {0}. Underlying error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2040700
Error occurred searching for user loginId with user key {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040701
Error occurred searching for organization name with organization key {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040702
Error occurred searching for role name with role key {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040703
Error occurred searching for role category name with role category key {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040704
Error occurred searching for resource name with resource key {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040705
Error occurred searching for user key with loginId {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040706
Error occurred searching for organization key with organization name {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040707
Error occurred searching for role key with role name {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040709
Error occurred searching for resource key with resource name {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040710
Error occurred during import of Approval Policy in Post Handler.Exception is {0}

Category:
Logging

Cause:

Action:

IAM-2040719
Error occurred while searching for application instance name with application instance key {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040720
Error occurred while searching for application instance key with application instance name {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040721
An error occurred while updating request data with orchestration parameters before approval initiation for request {0}. The corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2040724
Organization attribute is not set for request with request ID {0}

Category:
Logging

Cause:

Action:

IAM-2040725
Account key {0} not found.

Category:
Logging

Cause:

Action:

IAM-2040726
Error occurred while getting account details account key {0}.

Category:
Logging

Cause:

Action:

IAM-2040751
Error occurred importing Approval Policy {0}.Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2040752
Error occurred while getting catalog details for catalog id {0}.

Category:
Logging

Cause:

Action:

IAM-2050003
An error occurred while creating the database connection. The corresponding error message is {0}.

Category:
Logging

Cause:

Action:

IAM-2050004
An error occurred while saving the context of request {0}. The corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050007
An error occurred while completing approval process instance {0}. The corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050011
An error occurred while getting the model definition of request model {0}. The corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050014
An error occurred while initiating approvals for request {0}. The corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050024
An error occurred while executing plug-ins on status {0} to change for the request Id {1}.

Category:
Logging

Cause:

Action:

IAM-2050025
An error occurred while loading pre-population adapter {0} for an attribute {1}.

Category:
Logging

Cause:

Action:

IAM-2050026
No pre-population adapter is associated with the attribute {0}. Hence, returning null.

Category:
Logging

Cause:

Action:

IAM-2050027
An error occurred during pre-population of attribute {0}. Pre-population adapter {1} is not registered with the Plug-in Framework.

Category:
Logging

Cause:

Action:

IAM-2050028
An error occurred while getting a request data set. An entity type is not specified for the model {0},which is based on generic entity.

Category:
Logging

Cause:

Action:

IAM-2050029
An error occurred while getting a request data set. Model {0} is not based on a generic entity.

Category:
Logging

Cause:

Action:

IAM-2050030
Failed to get the request data set {0} from MDS with the error {1}.

Category:
Logging

Cause:

Action:

IAM-2050031
Failed to parse the request data set XML {0}. The corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050032
Request data-set {0} was not found in MDS.

Category:
Logging

Cause:

Action:

IAM-2050033
{1} request cannot set or change attribute {0}, since it is not defined in the corresponding data set.

Category:
Logging

Cause:

Action:

IAM-2050037
An error occurred while updating dependsOn attribute with value {0} for request with id {1} .

Category:
Logging

Cause:

Action:

IAM-2050038
An error occurred while retrieving dependent requests for request with id {0}.

Category:
Logging

Cause:

Action:

IAM-2050041
An error occurred while generating the request ID.

Category:
Logging

Cause:

Action:

IAM-2050042
No beneficiaries or target entities found in the request.

Category:
Logging

Cause:

Action:

IAM-2050043
Request model {0} does not support bulk requests.

Category:
Logging

Cause:

Action:

IAM-2050044
Invalid request data was found while performing validation.

Category:
Logging

Cause:

Action:

IAM-2050045
Failed while validating request data.

Category:
Logging

Cause:

Action:

IAM-2050050
Exception thrown {0}

Category:
Logging

Cause:

Action:

IAM-2050051
More than one request ID generation plug-in was found. Hence, returning null for the request ID.

Category:
Logging

Cause:

Action:

IAM-2050054
The beneficiary does not exist as part of the request data.

Category:
Logging

Cause:

Action:

IAM-2050055
No data set exists for request type {0} and entity type {1}. Consequently, no attributes can be specified as part of request data.

Category:
Logging

Cause:

Action:

IAM-2050057
Attribute(s) {0} is not available in bulk mode.

Category:
Logging

Cause:

Action:

IAM-2050058
The beneficiary should not be included as part of the request data for the request type {0}.

Category:
Logging

Cause:

Action:

IAM-2050060
Type is not specified for the attribute {0}.

Category:
Logging

Cause:

Action:

IAM-2050061
Type mismatch for the attribute {0}. The type passed is {1}, but the corresponding type in the data set is {2}.

Category:
Logging

Cause:

Action:

IAM-2050062
The value of the attribute {0} is not of the required type {1}.

Category:
Logging

Cause:

Action:

IAM-2050063
Attribute {0} has null value. It should have a non-null value.

Category:
Logging

Cause:

Action:

IAM-2050064
Entity Details are not specified for all beneficiary users.

Category:
Logging

Cause:

Action:

IAM-2050065
An authenticated user is trying to file a request using Request Model {0} that does not require login.

Category:
Logging

Cause:

Action:

IAM-2050067
Bulk Requests cannot be raised for the request type {0}.

Category:
Logging

Cause:

Action:

IAM-2050068
An error occurred while getting validation plug-in instance {0} for data set {1}.

Category:
Logging

Cause:

Action:

IAM-2050069
Log-in required to file the request using {0} Request Model and {1} Request Template.

Category:
Logging

Cause:

Action:

IAM-2050070
An unauthenticated user is trying to file a request using {0} Request Model and {1} Request Template.

Category:
Logging

Cause:

Action:

IAM-2050071
Failed to parse history XML with the error {0}.

Category:
Logging

Cause:

Action:

IAM-2050072
The request with the ID {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-2050073
An error occurred while getting approval tasks for the request {0}. The error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050074
An error occurred while getting the user {0} group membership. The corresponding error message is {0}.

Category:
Logging

Cause:

Action:

IAM-2050075
User {0} does not have permissions on the request {1}.

Category:
Logging

Cause:

Action:

IAM-2050076
No request found with the request ID {0}.

Category:
Logging

Cause:

Action:

IAM-2050077
An error occurred while fetching request ID {0} from the repository.

Category:
Logging

Cause:

Action:

IAM-2050078
An error occurred while fetching the request dataset for the request ID {0}.

Category:
Logging

Cause:

Action:

IAM-2050079
An error occurred while adding comments for request {0}. The corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050080
An error occurred while getting comments for request {0}. The corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050081
Invalid search criteria provided.

Category:
Logging

Cause:

Action:

IAM-2050082
An error occurred while searching for requests. The corresponding error message is {0}.

Category:
Logging

Cause:

Action:

IAM-2050084
User {0} can not {1} request {2} currently in {3} stage.

Category:
Logging

Cause:

Action:

IAM-2050085
Error while withdrawing request {0} and the corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050088
While populating additional fields of payload, an error occurred while loading the plug-in {0} associated with the approval process {1}.

Category:
Logging

Cause:

Action:

IAM-2050089
An error occurred while getting the user login attribute given key {0}.

Category:
Logging

Cause:

Action:

IAM-2050091
An error occurred while getting comments for the request with ID {0}.

Category:
Logging

Cause:

Action:

IAM-2050092
An error occurred while adding comments for the request with ID {0}.

Category:
Logging

Cause:

Action:

IAM-2050093
Unauthenticated user does not have access to the request model {0}.

Category:
Logging

Cause:

Action:

IAM-2050098
Missing required attribute(s) {0}.

Category:
Logging

Cause:

Action:

IAM-2050099
The length of the attribute value {0} is greater than the maximum allowed length {1}.

Category:
Logging

Cause:

Action:

IAM-2050100
Schema {0} not found. Validation did not complete for the Request model {1}.

Category:
Logging

Cause:

Action:

IAM-2050101
Schema {0} not found. Validation did not complete for the Request Dataset {1}.

Category:
Logging

Cause:

Action:

IAM-2050102
More than one entity type is selected for {0}

Category:
Logging

Cause:

Action:

IAM-2050103
Request ID specified is invalid.

Category:
Logging

Cause:

Action:

IAM-2050106
Failed to create payload XML. Error {0}.

Category:
Logging

Cause:

Action:

IAM-2050112
An error occurred while getting request stages. The corresponding error message is {0}.

Category:
Logging

Cause:

Action:

IAM-2050113
No request found with the request Key {0}.

Category:
Logging

Cause:

Action:

IAM-2050114
The beneficiary with beneficiary key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-2050115
Failed to get beneficiary details for beneficiary key {0} while validating request data.

Category:
Logging

Cause:

Action:

IAM-2050117
System-type attribute(s) {0} cannot be specified in request.

Category:
Logging

Cause:

Action:

IAM-2050120
An error occurred while updating the request with approver data. Request with id {0} is not found.

Category:
Logging

Cause:

Action:

IAM-2050121
An error occurred while updating the request with approver data. Either valid beneficiary information or valid entity information is required.

Category:
Logging

Cause:

Action:

IAM-2050122
An error occurred while updating the request with approver data. Request with id {0} is in {1} stage.

Category:
Logging

Cause:

Action:

IAM-2050123
An error occurred while updating the request with approver data. Beneficiary information is required.

Category:
Logging

Cause:

Action:

IAM-2050124
An error occurred while updating the request with approver data. Entity information is required.

Category:
Logging

Cause:

Action:

IAM-2050125
Information for {0} was not filled in by the approver.

Category:
Logging

Cause:

Action:

IAM-2050126
Invalid outcome {0} received from SOA for the request id {1}.

Category:
Logging

Cause:

Action:

IAM-2050127
Invalid Request Data for Self-Request. Cannot have multiple beneficiaries.

Category:
Logging

Cause:

Action:

IAM-2050128
Invalid beneficiary key was specified for Self-Request.

Category:
Logging

Cause:

Action:

IAM-2050129
Invalid Request Data for Self Request. Cannot have multiple targets.

Category:
Logging

Cause:

Action:

IAM-2050130
An invalid target-entity key was specified for the Self-Request.

Category:
Logging

Cause:

Action:

IAM-2050131
A Request Beneficiary entity key was not specified for the beneficiary {0}.

Category:
Logging

Cause:

Action:

IAM-2050132
A Request Beneficiary entity Sub-type was not specified for the beneficiary {0}.

Category:
Logging

Cause:

Action:

IAM-2050133
A Request Beneficiary entity key and Sub-type were not specified for the beneficiary {0}.

Category:
Logging

Cause:

Action:

IAM-2050136
Logged-in user does not have permission to update Request status for request {0}.

Category:
Logging

Cause:

Action:

IAM-2050137
Failed to update the Request status for the request [key = {0}] in the repository.

Category:
Logging

Cause:

Action:

IAM-2050138
Request dataset provider plugin {0} is not found.

Category:
Logging

Cause:

Action:

IAM-2050139
Request model {0} and {1} are associated with same entity type and operation.

Category:
Logging

Cause:

Action:

IAM-2050140
Operation being performed is not supported without approvals.

Category:
Logging

Cause:

Action:

IAM-2050141
User {0} is not allowed to perform this operation.

Category:
Logging

Cause:

Action:

IAM-2050142
Error occurred while fetching SODCheckObligation plugins from Plugin Registry.

Category:
Logging

Cause:

Action:

IAM-2050143
Error occurred while fetching plugin instance of type SODCheckObligation plugin.

Category:
Logging

Cause:

Action:

IAM-2050144
User {0} is not allowed to be part of {1} operation involving {2} with name {3}.

Category:
Logging

Cause:

Action:

IAM-2050145
Error occurred while performing authorization check for beneficiary. Beneficiary Key is not specified in the data.

Category:
Logging

Cause:

Action:

IAM-2050146
Error occurred while performing authorization check for beneficiary. Target entity Key is not specified for beneficiary {0}.

Category:
Logging

Cause:

Action:

IAM-2050147
Request with ID {0} is closed successfully.

Category:
Logging

Cause:

Action:

IAM-2050148
Request with key {0} is already closed or withdrawn.

Category:
Logging

Cause:

Action:

IAM-2050149
Request submission failed with Error {0}.

Category:
Logging

Cause:

Action:

IAM-2050150
Validation failed with error message {0}

Category:
Logging

Cause:

Action:

IAM-2050151
Multiple plugins registered for {0}. Registered Plugins are {1}

Category:
Logging

Cause:

Action:

IAM-2050152
Unknown Request Permission Type {0}.

Category:
Logging

Cause:

Action:

IAM-2050153
Pending approval instance exists for request with id {0}, that is being closed or withdrawn while SOA is turned off.

Category:
Logging

Cause:

Action:

IAM-2050154
Logged-in user does not have permission to publish role to organizations - {0}.

Category:
Logging

Cause:

Action:

IAM-2050155
Logged-in user does not have permission to publish role to sub-organizations of - {0}.

Category:
Logging

Cause:

Action:

IAM-2050200
Failed to create the request in the repository.

Category:
Logging

Cause:

Action:

IAM-2050201
Failed to update the request ID for the request [key = {0}] in the repository.

Category:
Logging

Cause:

Action:

IAM-2050202
Failed to update the stage and status for the request [key = {0}] in the repository.

Category:
Logging

Cause:

Action:

IAM-2050203
Failed to update the orchestration process ID for the request [key = {0}] in the repository.

Category:
Logging

Cause:

Action:

IAM-2050204
Failed to update the context ID for the request [key = {0}] in the repository.

Category:
Logging

Cause:

Action:

IAM-2050205
Failed to update the orchestration event ID for the request [key = {0}] in the repository.

Category:
Logging

Cause:

Action:

IAM-2050206
Failed to update the request end-date for the request [key = {0}] in the repository.

Category:
Logging

Cause:

Action:

IAM-2050208
Error occurred while generating orchestration parameters using plugin form request model {0} and request [key = {1}]

Category:
Logging

Cause:

Action:

IAM-2050210
Error while loading Orchestration plug-in class of request model {0} for the request [key = {1}].

Category:
Logging

Cause:

Action:

IAM-2050211
Failed to update the request [ID = {0}] in the repository.

Category:
Logging

Cause:

Action:

IAM-2050212
An error occurred while retrieving requests awaiting execution from the repository.

Category:
Logging

Cause:

Action:

IAM-2050214
Failed to update the error for the request [key = {0}].

Category:
Logging

Cause:

Action:

IAM-2050215
Invalid attribute {0} for request beneficiary data update was discarded.

Category:
Logging

Cause:

Action:

IAM-2050216
No updated attributes for request beneficiary data update.

Category:
Logging

Cause:

Action:

IAM-2050220
Orchestration failed for request Id {0} and the corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050221
Orchestration process with Id {0} failed for request Id {1} and the corresponding error message is {2}.

Category:
Logging

Cause:

Action:

IAM-2050222
Logged in user with key {0} does not have access to view requests of user with key {1}.

Category:
Logging

Cause:

Action:

IAM-2050223
Incorrect Execution Date is provided for the request. Execution date allowed is current date or later.

Category:
Logging

Cause:

Action:

IAM-2050224
User {0} cannot {1} request {2} as child request {3} is in {4} stage.

Category:
Logging

Cause:

Action:

IAM-2050225
An error occurred while getting request comments because invalid criteria was provided.

Category:
Logging

Cause:

Action:

IAM-2050226
No instance selected.

Category:
Logging

Cause:

Action:

IAM-2050227
Error occurred while updating approver-only data. Attribute {0} is not an approver-only attribute.

Category:
Logging

Cause:

Action:

IAM-2050228
Error occurred while updating approver-only data. Value not specified for mandatory attribute {0}.

Category:
Logging

Cause:

Action:

IAM-2050229
Error occurred while updating approver-only data. Please update all approver-only attributes defined in the dataset.

Category:
Logging

Cause:

Action:

IAM-2050230
Beneficiary Type is not set for beneficiary {0}

Category:
Logging

Cause:

Action:

IAM-2050231
No request type found for entity type {0} and operation {1}.

Category:
Logging

Cause:

Action:

IAM-2050232
Attribute {0} is multi valued. Value field used for setting single value should not be used.

Category:
Logging

Cause:

Action:

IAM-2050233
Multiple values are provided for the attribute {0}. The attribute is not configured as multi valued.

Category:
Logging

Cause:

Action:

IAM-2050234
User with the id {0} does not have permissions to update request with id {1}.

Category:
Logging

Cause:

Action:

IAM-2050235
Child attributes found for attribute {0}. Updating child attribute data is not supported.

Category:
Logging

Cause:

Action:

IAM-2050236
Attribute {0} is configured as system type and can not be updated by approver.

Category:
Logging

Cause:

Action:

IAM-2050237
User with id {0} is not authorized to modify user attribute(s) {1}.

Category:
Logging

Cause:

Action:

IAM-2050238
Error occurred while updating request with id{0}. No matching entity found with entity type {1} and operation {2}.

Category:
Logging

Cause:

Action:

IAM-2050239
Error occurred while updating request with id{0}. Corresponding error messages is {1}.

Category:
Logging

Cause:

Action:

IAM-2050240
User with id {0} is not authorized to provide values to attribute(s) {1} during create user operation.

Category:
Logging

Cause:

Action:

IAM-2050241
Direct bulk operation is not allowed.

Category:
Logging

Cause:

Action:

IAM-2050243
Orchestration process with id {0}, failed with error message {1}.

Category:
Logging

Cause:

Action:

IAM-2050244
Request can not be created with the deprecated request type {0}.

Category:
Logging

Cause:

Action:

IAM-2050245
Request can not be created with heterogeneous RequestEntity types.

Category:
Logging

Cause:

Action:

IAM-2050246
Attribute {0} is a required attribute, value must be nonempty string.

Category:
Logging

Cause:

Action:

IAM-2050247
No attributes are updated.

Category:
Logging

Cause:

Action:

IAM-2050248
Failed to load certification resolver plugin with error message {0}.

Category:
Logging

Cause:

Action:

IAM-2050249
User {0} does not have access to view revoke requests of certification with id {1}.

Category:
Logging

Cause:

Action:

IAM-2050250
Failed to delete request data for request id {0}.

Category:
Logging

Cause:

Action:

IAM-2050251
Request with id {0} cannot be deleted since this is not in draft state.

Category:
Logging

Cause:

Action:

IAM-2050252
Logged in user {0} does not have permission to delete the request with id {1}.

Category:
Logging

Cause:

Action:

IAM-2050253
Request with id {0} cannot be updated since this is not in draft state.

Category:
Logging

Cause:

Action:

IAM-2050254
No request model found for the draft request id {0}.

Category:
Logging

Cause:

Action:

IAM-2050255
Logged in user {0} does not have permission to update the request with id {1}.

Category:
Logging

Cause:

Action:

IAM-2050256
Request with id {0} cannot be resubmitted as it is not in Draft State.

Category:
Logging

Cause:

Action:

IAM-2050257
Logged in user {0} does not have permission to submit the request with id {1}.

Category:
Logging

Cause:

Action:

IAM-2050258
An error occurred while updating the request history for the request key {0}. The corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050259
An error occurred while serializing/de-serializing RequestDataSet object with the error {0}.

Category:
Logging

Cause:

Action:

IAM-2050260
Generated request Id {0} is not alphanumeric.

Category:
Logging

Cause:

Action:

IAM-2050261
No target entities found in the request.

Category:
Logging

Cause:

Action:

IAM-2050300
Logged-in user does not have permission to create request data set.

Category:
Logging

Cause:

Action:

IAM-2050301
Failed to validate the request data set {0}.

Category:
Logging

Cause:

Action:

IAM-2050302
Request data set creation failed with error{0}.

Category:
Logging

Cause:

Action:

IAM-2050304
Logged-in user does not have permission to update request data set.

Category:
Logging

Cause:

Action:

IAM-2050305
Logged-in user does not have permission to delete request data set.

Category:
Logging

Cause:

Action:

IAM-2050306
Request data set deletion failed with error {0}.

Category:
Logging

Cause:

Action:

IAM-2050307
Request data set update failed with error {0}.

Category:
Logging

Cause:

Action:

IAM-2050308
The request data set with name {0} already exists in the MDS.

Category:
Logging

Cause:

Action:

IAM-2050310
Logged-in user does not have permission to list the request data sets.

Category:
Logging

Cause:

Action:

IAM-2050311
Invalid Entity Type {0} or entity name {1}

Category:
Logging

Cause:

Action:

IAM-2050500
An error occurred while creating the Approval Policy {0}.

Category:
Logging

Cause:

Action:

IAM-2050501
An error occurred while modifying the Approval Policy {0}.

Category:
Logging

Cause:

Action:

IAM-2050502
An error occurred while deleting the Approval Policy id {0}.

Category:
Logging

Cause:

Action:

IAM-2050503
The rule evaluation with expression {0} failed because the attribute was not found in the target object.

Category:
Logging

Cause:

Action:

IAM-2050504
An error occurred evaluating Ognl expression {0}.

Category:
Logging

Cause:

Action:

IAM-2050505
An error occurred while putting Approval Policy information in Context Manager.

Category:
Logging

Cause:

Action:

IAM-2050506
An error occurred framing the Approval Policy Rule for {0}.

Category:
Logging

Cause:

Action:

IAM-2050507
An error occurred while getting the {0} information for the Approval Policy Rule evaluation at {1}.

Category:
Logging

Cause:

Action:

IAM-2050509
An error occurred while searching for organizations.

Category:
Logging

Cause:

Action:

IAM-2050510
An error occurred while searching for user attributes.

Category:
Logging

Cause:

Action:

IAM-2050511
An error occurred while searching for obj_key for resource {0}.

Category:
Logging

Cause:

Action:

IAM-2050512
An error occurred while searching for process form details for oiu_key {0}.

Category:
Logging

Cause:

Action:

IAM-2050513
An error occurred while searching for resource object details.

Category:
Logging

Cause:

Action:

IAM-2050514
An error occurred while searching for user details with the key {0}

Category:
Logging

Cause:

Action:

IAM-2050515
An error occurred while searching request model {0}

Category:
Logging

Cause:

Action:

IAM-2050516
An error occurred while searching the data-set associated with request model {0} and entity {1}.

Category:
Logging

Cause:

Action:

IAM-2050517
An error occurred while searching for the request class.

Category:
Logging

Cause:

Action:

IAM-2050518
An error occurred while modifying the Approval Policy. Stale data was found while modifying or deleting the Approval Policy ID {0}.

Category:
Logging

Cause:

Action:

IAM-2050519
An error occurred while loading the Approval Policy UI Helper Plug-in.

Category:
Logging

Cause:

Action:

IAM-2050520
An error occurred while searching for the user key with the userID {0}.

Category:
Logging

Cause:

Action:

IAM-2050521
User {0} does not have access to {1} entity of type {2}.

Category:
Logging

Cause:

Action:

IAM-2050522
Approval Policy name {0} contains invalid characters.

Category:
Logging

Cause:

Action:

IAM-2050523
An error occurred while retrieving entity details.

Category:
Logging

Cause:

Action:

IAM-2050524
An error occurred while creating Approval Policy name {0}. There already exists a policy with name {1}.

Category:
Logging

Cause:

Action:

IAM-2050525
An error occurred while creating an Approval Policy with null value {0}.

Category:
Logging

Cause:

Action:

IAM-2050526
ScopeTypeValue, ScopeValue, and ScopeConditionOperator parameter cannot be NULL when setting scopeBasedConditionClause.

Category:
Logging

Cause:

Action:

IAM-2050527
Invalid value for ScopeTypeValue parameter. Valid values include 0 for Organization, 1 for Resource, and 2 for Role Scope.

Category:
Logging

Cause:

Action:

IAM-2050528
Invalid value for Scope Comparator parameter. When ScopeTypevalue parameter is for Application Instance (1) or Resource (2) or Role (3), the only valid parameter values for scopeComparator are EQUAL, CONTAIN, BEGIN_WITH, and END_WITH.

Category:
Logging

Cause:

Action:

IAM-2050529
Invalid attribute {0} passed in approval policy search criteria.

Category:
Logging

Cause:

Action:

IAM-2050530
Invalid value for Scope Type Comparator parameter. The only valid parameter value for Scope Type Comparator is EQUAL.

Category:
Logging

Cause:

Action:

IAM-2050532
An error occurred while searching for the role with key {0}.

Category:
Logging

Cause:

Action:

IAM-2050534
An error occurred while evaluating a set of approval policies for the approval process.

Category:
Logging

Cause:

Action:

IAM-2050535
An error occurred while searching for role details with key {0}.

Category:
Logging

Cause:

Action:

IAM-2050538
An error occurred while searching for the RoleCategory name with key {0}.

Category:
Logging

Cause:

Action:

IAM-2050539
An error occurred while searching for the organization key with name {0}.

Category:
Logging

Cause:

Action:

IAM-2050540
An error occurred while searching for the user key with loginId {0}.

Category:
Logging

Cause:

Action:

IAM-2050541
An error occurred while searching for the RoleCategory key with RoleCategory Name {0}.

Category:
Logging

Cause:

Action:

IAM-2050542
An error occurred while configuring the Approval Policy with the request model name {0}.

Category:
Logging

Cause:

Action:

IAM-2050543
Invalid Auto-Approval configuration for Self-Register model at Request Level.

Category:
Logging

Cause:

Action:

IAM-2050544
Error occurred while finding resource objects. Underlying error messages is {0}

Category:
Logging

Cause:

Action:

IAM-2050545
Error occurred while searching for user details with user login {0}.

Category:
Logging

Cause:

Action:

IAM-2050546
Invalid approval policy ids passed for approval policy delete operation.

Category:
Logging

Cause:

Action:

IAM-2050547
An error occurred while searching for the application instance with the key {0}.

Category:
Logging

Cause:

Action:

IAM-2050548
An error occurred while searching for the entitlement with the key {0}

Category:
Logging

Cause:

Action:

IAM-2050552
An error occurred while searching for the role {0}.

Category:
Logging

Cause:

Action:

IAM-2050553
This operation is not supported.

Category:
Logging

Cause:

Action:

IAM-2050600
User {0} cannot {1} request {2} as dependent request {3} is in {4} stage.

Category:
Logging

Cause:

Action:

IAM-2050601
Request with Id {0} failed since the depends on request with id {1} is failed.

Category:
Logging

Cause:

Action:

IAM-2050602
Related application instance {0} and entitlement {1} can not be requested together.

Category:
Logging

Cause:

Action:

IAM-2050603
An error occurred while searching application instances with keys {0}. Exception is {1}

Category:
Logging

Cause:

Action:

IAM-2050604
An error occurred while searching entitlements with keys {0}. Exception is {1}.

Category:
Logging

Cause:

Action:

IAM-2050605
An error occurred while searching application instance with object key {0} and ITResource key {1} . Exception is {2}

Category:
Logging

Cause:

Action:

IAM-2050606
An error occurred while searching entitlement with key {0}. Exception is {1}.

Category:
Logging

Cause:

Action:

IAM-2050607
Invalid dependency set from entitlement {0} to application instance {1}.

Category:
Logging

Cause:

Action:

IAM-2050720
Error while searching for roles.

Category:
Logging

Cause:

Action:

IAM-2050903
Auto registration of approval process {0} failed while creating policy {1}.

Category:
Logging

Cause:

Action:

IAM-2050904
Approval Process {0} configured with policy {1} is disabled.

Category:
Logging

Cause:

Action:

IAM-2050905
Approval Process {0} auto registered.

Category:
Logging

Cause:

Action:

IAM-2050950
An error occurred while initiating provide information workflow for request with id {0}. The corresponding error message is {1}.

Category:
Logging

Cause:

Action:

IAM-2050951
Provided information workflow can be initiated only for requests in status Request Created. Request with id {0} is in status {1}.

Category:
Logging

Cause:

Action:

IAM-2050952
User Id parameter passed cannot be null or empty

Category:
Logging

Cause:

Action:

IAM-2052001
An error occurred while creating the child request for the request with key {0}

Category:
Logging

Cause:

Action:

IAM-2053001
User {0} does not have access to {1} {2}.

Category:
Logging

Cause:

Action:

IAM-2053002
User {0} does not have view permission on User {1}.

Category:
Logging

Cause:

Action:

IAM-2053004
Name property has not been specified for an Additional attribute.

Category:
Logging

Cause:

Action:

IAM-2053005
Type property has not been specified for Additional attribute {0}.

Category:
Logging

Cause:

Action:

IAM-2053006
Invalid value {0} has been specified for Additional attribute {1} of TYPE {2}.

Category:
Logging

Cause:

Action:

IAM-2053007
Value of Additional attribute {0} exceeds maximum alowed length of 4000 characters.

Category:
Logging

Cause:

Action:

IAM-2053008
Masked values are not allowed for additional attribute {0}.

Category:
Logging

Cause:

Action:

IAM-2053009
MLS values are not allowed for additional attribute {0}.

Category:
Logging

Cause:

Action:

IAM-2053010
Request dataset validators are not configured for {0}.

Category:
Logging

Cause:

Action:

IAM-2053011
Error occurred while evaluating workflow policies. Could not determine if {0} operation requires approvals. Corresponding error message is: {1}.

Category:
Logging

Cause:

Action:

IAM-2053020
Error occurred while loading workflow policies configured in the system. Corresponding error message is: {0}.

Category:
Logging

Cause:

Action:

IAM-2053021
Error occurred while evaluating Workflow Policy with ID {0}. Corresponding error message is: {1}.

Category:
Logging

Cause:

Action:

IAM-2053022
Error occurred while fetching Workflow Policy type definitions. Corresponding error message is: {0}.

Category:
Logging

Cause:

Action:

IAM-2053023
Workflow Policy type definitions are not found in the system.

Category:
Logging

Cause:

Action:

IAM-2053024
Workflow Policies are not found in the system.

Category:
Logging

Cause:

Action:

IAM-2053025
PolicyType Configuration Error. Invalid input type {0} found in the policy type {1}.

Category:
Logging

Cause:

Action:

IAM-2053026
Error occurred while populating ValueObject with {0} entity data for key {1}. Corresponding error message is: {2}.

Category:
Logging

Cause:

Action:

IAM-2053027
Error occurred while populating ValueObject with User"s roles for user key {0}. Corresponding error message is: {1}.

Category:
Logging

Cause:

Action:

IAM-2053029
Error occurred while populating ValueObject with {0} data. Corresponding error message is: {1}.

Category:
Logging

Cause:

Action:

IAM-2053030
Error occurred while populating ValueObject with Catalog metadata for {0} entity with Key {1}. Corresponding error message is: {2}.

Category:
Logging

Cause:

Action:

IAM-2053031
No Catalog Metadata found for {0} with Key {1}.

Category:
Logging

Cause:

Action:

IAM-2053032
Cannot populate input ValueObject with catalog Metadata for {0} with key {1} as the key is invalid.

Category:
Logging

Cause:

Action:

IAM-2053033
Workflow rule evaluation would be skipped for {0} operation, as corresponding workflow policy or type does not exist.

Category:
Logging

Cause:

Action:

IAM-2053034
Workflow rule evaluation would be skipped for operation, because the system could not determine the request type. Corresponding error message is: {0}.

Category:
Logging

Cause:

Action:

IAM-2055500
Invalid search parameter {0}. "%" not allowed.

Category:
Logging

Cause:

Action:

IAM-2060000
The reversed string is {0}, Good Luck!

Category:
Logging

Cause:

Action:

IAM-2060002
Error occurred while submitting information for task from BPEL

Category:
Logging

Cause:

Action:

IAM-2060003
Error occurred while requesting information for task from BPEL

Category:
Logging

Cause:

Action:

IAM-2060004
Error occurred while rejecting task from BPEL

Category:
Logging

Cause:

Action:

IAM-2060005
Error occurred while loading actions from BPEL

Category:
Logging

Cause:

Action:

IAM-2060006
Error occurred while re-assigning task from BPEL

Category:
Logging

Cause:

Action:

IAM-2060007
Error occurred while claiming task from BPEL

Category:
Logging

Cause:

Action:

IAM-2060008
Error occurred while updating approver only data from BPEL

Category:
Logging

Cause:

Action:

IAM-2060009
Error occurred while approving task from BPEL

Category:
Logging

Cause:

Action:

IAM-2060010
Error occurred while getting request comments from RequestDetails

Category:
Logging

Cause:

Action:

IAM-2060011
Error occurred while searching for tasks from BPEL

Category:
Logging

Cause:

Action:

IAM-2060012
Error occurred while connecting to BPEL

Category:
Logging

Cause:

Action:

IAM-2060013
Exception thrown:

Category:
Logging

Cause:

Action:

IAM-2070000
An error occurred while invoking OAACG and corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-2070003
An error occurred while finding the applicability of InvokeOAACGSODCheck event handler and corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-2070004
OAACG SOD Check composite with name {0} is successfully invoked and instance id is {1}

Category:
Logging

Cause:

Action:

IAM-2070005
OAACG SOD Check composite with name {0} invocation failed and corresponding error is - {1}

Category:
Logging

Cause:

Action:

IAM-2070006
No Authorization issues found to callback OAACG

Category:
Logging

Cause:

Action:

IAM-2070007
An error occurred while notifying OAACG with OIM approval decision and corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-2070008
An error occurred while finding the request details and corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-2070009
OAACG Issues that will be approved by OIM are - {0}

Category:
Logging

Cause:

Action:

IAM-2070010
OAACG Issues that will be rejected by OIM are - {0}

Category:
Logging

Cause:

Action:

IAM-2070012
An error occurred while retrieving the SOD conflicts and corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-2070013
An error occurred while notifying OIM of SOD approval decision - {0}

Category:
Logging

Cause:

Action:

IAM-2070014
Got Issue status override confirmation

Category:
Logging

Cause:

Action:

IAM-2070015
An error occurred while getting the recipient key alias

Category:
Logging

Cause:

Action:

IAM-2070016
Failed to create payload XML. Error {0}.

Category:
Logging

Cause:

Action:

IAM-2070017
An error occurred while searching for user details with the key {0}

Category:
Logging

Cause:

Action:

IAM-2070018
An error occurred while checking if role with id {0} is an OOTB role or not and corresponding error message is - {1}

Category:
Logging

Cause:

Action:

IAM-2070019
An error occurred while storing the SOD conflicts and corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-2070020
An error occurred while storing approver comment and corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-2090001
Creation of Request Profile {0} is failed with error {1}.

Category:
Logging

Cause:

Action:

IAM-2090002
User {0} does not have access to {1} entity of type {2}.

Category:
Logging

Cause:

Action:

IAM-2090003
Request Profile name contains invalid characters.

Category:
Logging

Cause:

Action:

IAM-2090004
Deletion of Request Profile {0} is failed with error {1}.

Category:
Logging

Cause:

Action:

IAM-2090005
Stale data found for profile {0}.

Category:
Logging

Cause:

Action:

IAM-2090006
Modification of Request Profile {0} is failed with error {1}.

Category:
Logging

Cause:

Action:

IAM-2090007
Retrieval of Request Profile {0} is failed with error {1}.

Category:
Logging

Cause:

Action:

IAM-2090008
Searching Request Profile having {0} name pattern is failed with error {1}.

Category:
Logging

Cause:

Action:

IAM-2090009
Could not delete the Request Profile {0}.

Category:
Logging

Cause:

Action:

IAM-2090010
Exception thrown {0}.

Category:
Logging

Cause:

Action:

IAM-2090011
Could not create Request Profile {0} with empty cart.

Category:
Logging

Cause:

Action:

IAM-2090012
Could not modify Request Profile {0} with out any cart items.

Category:
Logging

Cause:

Action:

IAM-3010000
Cannot initialize the LDAPSync Util - {0}.

Category:
Logging

Cause:

Action:

IAM-3010001
A user with the key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3010003
Failed to execute the handler.

Category:
Logging

Cause:

Action:

IAM-3010004
An error occurred while deleting LDAP user in the compensate stage.

Category:
Logging

Cause:

Action:

IAM-3010006
An error occurred while retrieving USR_ROWVER for user (key: {0}). Setting USR_ROWVER to null.

Category:
Logging

Cause:

Action:

IAM-3010007
The key found in the context ({0}) is invalid. Setting change reason key to 0.

Category:
Logging

Cause:

Action:

IAM-3010008
An error occurred while preparing to audit data for user (key: {0}). Unable to set current user state - {1}

Category:
Logging

Cause:

Action:

IAM-3010009
An error occurred while preparing to audit data for user (key: {0}). Unable to set current user state - {1}

Category:
Logging

Cause:

Action:

IAM-3010010
An error occurred while retrieving user entity data (key: {0}) - {1}

Category:
Logging

Cause:

Action:

IAM-3010011
An error occurred while updating GUID, DN for user (key: {0}) - {1}

Category:
Logging

Cause:

Action:

IAM-3010012
An error occurred while retrieving UGP_ROWVER for role (key: {0}). Setting UGP_ROWVER to null.

Category:
Logging

Cause:

Action:

IAM-3010013
An error occurred while preparing to audit data for role (key: {0}). Unable to set current role state - {1}

Category:
Logging

Cause:

Action:

IAM-3010014
An error occurred while preparing to audit data for role (key: {0}). Unable to set current role state - {1}

Category:
Logging

Cause:

Action:

IAM-3010015
An error occurred while retrieving role entity data (key: {0}) - {1}

Category:
Logging

Cause:

Action:

IAM-3010016
An error occurred while updating GUID, DN for role (key: {0} - {1}

Category:
Logging

Cause:

Action:

IAM-3010017
No roles received to compensate.

Category:
Logging

Cause:

Action:

IAM-3010018
A role with the key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3010019
An error occurred while initializing the LDAP sync data provider.

Category:
Logging

Cause:

Action:

IAM-3010020
Could not retrieve the user id of the reserved user.

Category:
Logging

Cause:

Action:

IAM-3010021
An error occurred while creating the user in LDAP.

Category:
Logging

Cause:

Action:

IAM-3010022
Failed to compensate

Category:
Logging

Cause:

Action:

IAM-3010023
Failed to compensate disabling of user(s) in LDAP with key(s) - {0}

Category:
Logging

Cause:

Action:

IAM-3010024
An error occurred while disabling user(s) in LDAP with key(s) - {0}

Category:
Logging

Cause:

Action:

IAM-3010025
Failed to compensate enabling of user(s) in LDAP with keys - {0}

Category:
Logging

Cause:

Action:

IAM-3010026
An error occurred while enabling user(s) in LDAP with key(s) - {0}

Category:
Logging

Cause:

Action:

IAM-3010027
Failed to compensate deleting user(s) in LDAP with keys - {0}

Category:
Logging

Cause:

Action:

IAM-3010028
An error occurred while deleting user(s) in LDAP with key(s) - {0}

Category:
Logging

Cause:

Action:

IAM-3010029
Failed to compensate password reset of user in LDAP with key - {0}

Category:
Logging

Cause:

Action:

IAM-3010030
An error occurred while resetting password of user in LDAP with key - {0}

Category:
Logging

Cause:

Action:

IAM-3010031
Failed to compensate modify user(s) in LDAP with key(s)- {0}

Category:
Logging

Cause:

Action:

IAM-3010032
An error occurred while modifying user(s) in LDAP with key(s) - {0}

Category:
Logging

Cause:

Action:

IAM-3010033
Failed to compensate locking of user(s) in LDAP with keys - {0}

Category:
Logging

Cause:

Action:

IAM-3010034
An error occurred while locking user(s) in LDAP with keys - {0}

Category:
Logging

Cause:

Action:

IAM-3010035
Failed to compensate unlocking of user(s) in LDAP with keys - {0}

Category:
Logging

Cause:

Action:

IAM-3010036
An error occurred while unlocking user(s) in LDAP with keys - {0}

Category:
Logging

Cause:

Action:

IAM-3010037
An error occurred while processing the data that is retrieved from LDAP to create a reconciliation event.

Category:
Logging

Cause:

Action:

IAM-3010038
An error occurred while creating reconciliation event, and the corresponding message is - {0}

Category:
Logging

Cause:

Action:

IAM-3010039
An error occurred while handling parameters in the event handler.

Category:
Logging

Cause:

Action:

IAM-3010040
An error occurred while determining the LDAP container.

Category:
Logging

Cause:

Action:

IAM-3010041
An error occurred while determining the LDAP container mapping plug-in.

Category:
Logging

Cause:

Action:

IAM-3010042
Loading LDAP container mapping plug-in - {0}

Category:
Logging

Cause:

Action:

IAM-3010043
Failed to load LDAP container mapping rules.

Category:
Logging

Cause:

Action:

IAM-3010044
An error occurred while reading and parsing LDAP container mapping rules

Category:
Logging

Cause:

Action:

IAM-3010045
A malformed expression in LDAP container mapping rules occurred. Expression {0} will be ignored

Category:
Logging

Cause:

Action:

IAM-3010046
Cannot register the MDS change notification listener.

Category:
Logging

Cause:

Action:

IAM-3010047
An error occurred while initializing the schedule job - {0}, and the corresponding error message is - {1}

Category:
Logging

Cause:

Action:

IAM-3010048
An error occurred while initializing the event handler that adds missing LDAP object classes, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-3010049
An error occurred while adding additional object classes to user, and the corresponding error is - {0}

Category:
Logging

Cause:

Action:

IAM-3010051
Modification failed because the role with LDAP DN {0} does not exist in the directory.

Category:
Logging

Cause:

Action:

IAM-3010053
Modification failed because the user with LDAP DN {0} does not exist in the directory.

Category:
Logging

Cause:

Action:

IAM-3010054
Deletion failed because the user with LDAP DN {0} does not exist in the directory.

Category:
Logging

Cause:

Action:

IAM-3010055
Enabling failed because the user with LDAP DN {0} does not exist in the directory.

Category:
Logging

Cause:

Action:

IAM-3010056
Disabling failed because the user with LDAP DN {0} does not exist in the directory.

Category:
Logging

Cause:

Action:

IAM-3010057
Locking failed because the user with LDAP DN {0} does not exist in the directory.

Category:
Logging

Cause:

Action:

IAM-3010058
Unlocking failed because the user with LDAP DN {0} does not exist in the directory.

Category:
Logging

Cause:

Action:

IAM-3010059
Modification failed because user {0} is not synchronized to the LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010060
Deletion failed because user {0} is not synchronized to the LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010061
Enabling failed because user {0} is not synchronized to the LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010062
Disabling failed because user {0} is not synchronized to the LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010063
Locking failed because user {0} is not synchronized to the LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010064
Unlocking failed because user {0} is not synchronized to the LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010065
Modification failed because role {0} is not synchronized to the LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010066
Deletion failed because role {0} is not synchronized to the LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010067
Password reset failed because the user with LDAP DN {0} does not exist in the directory.

Category:
Logging

Cause:

Action:

IAM-3010068
Password reset failed because user {0} is not synchronized to the LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010069
An error occurred while creating or updating a role in LDAP during DM import.

Category:
Logging

Cause:

Action:

IAM-3010070
Adding user membership failed because role {0} is not synchronized to the LDAP directory

Category:
Logging

Cause:

Action:

IAM-3010071
Deletion of user membership failed because role {0} is not synchronized to the LDAP directory

Category:
Logging

Cause:

Action:

IAM-3010072
Adding user membership failed because user {0} is not synchronized to the LDAP directory

Category:
Logging

Cause:

Action:

IAM-3010073
Deletion of user membership failed because user {0} is not synchronized to the LDAP directory

Category:
Logging

Cause:

Action:

IAM-3010074
Adding role hierarchy failed because role {0} is not synchronized to the LDAP directory

Category:
Logging

Cause:

Action:

IAM-3010075
Deletion of role hierarchy failed because role {0} is not synchronized to the LDAP directory

Category:
Logging

Cause:

Action:

IAM-3010076
Adding user membership failed because the role with LDAP DN {0} does not exist in the directory

Category:
Logging

Cause:

Action:

IAM-3010077
Deletion of user membership failed because the role with LDAP DN {0} does not exist in the directory

Category:
Logging

Cause:

Action:

IAM-3010078
Adding user membership failed because the user with LDAP DN {0} does not exist in the directory

Category:
Logging

Cause:

Action:

IAM-3010079
Deletion of user membership failed because the user with LDAP DN {0} does not exist in the directory

Category:
Logging

Cause:

Action:

IAM-3010080
Adding role hierarchy failed because the role with LDAP DN {0} does not exist in the directory

Category:
Logging

Cause:

Action:

IAM-3010082
An error occurred while retrieving the value for system property {0}.

Category:
Logging

Cause:

Action:

IAM-3010083
An error occurred while decrypting value for the attribute {0} for user with user key {1}

Category:
Logging

Cause:

Action:

IAM-3010084
The {0} entity does not exist.

Category:
Logging

Cause:

Action:

IAM-3010085
An error occurred while searching for the user attributes in user metadata.

Category:
Logging

Cause:

Action:

IAM-3010086
Error occurred while doing lookup operation on {0} entity with ID {1}.

Category:
Logging

Cause:

Action:

IAM-3010087
An error occurred while searching for the user.

Category:
Logging

Cause:

Action:

IAM-3010089
Compensate method called in pre-process handler of user operation {0} with process Id {1} and event Id {2}

Category:
Logging

Cause:

Action:

IAM-3010090
An error occurred as there is no result or null returned from LDAP. Check the log files.

Category:
Logging

Cause:

Action:

IAM-3010091
Some errors occurred during LDAP data processing for which recon events were not created. The errors are: {0}

Category:
Logging

Cause:

Action:

IAM-3010092
An error occurred for DN {0} and GUID {1}: {2}.

Category:
Logging

Cause:

Action:

IAM-3010093
An error occurred for GUID {0}: {1}.

Category:
Logging

Cause:

Action:

IAM-3010094
An error occurred when deleting users/roles from OIM DB for Delete Full Reconciliation scheduler job.

Category:
Logging

Cause:

Action:

IAM-3010095
An error occurred in post processing handler when modifying user entry.

Category:
Logging

Cause:

Action:

IAM-3010096
An error occurred in post processing handler when creating user entry.

Category:
Logging

Cause:

Action:

IAM-3010097
An error occurred in post processing handler when creating role entry.

Category:
Logging

Cause:

Action:

IAM-3010098
An error occurred in post processing handler when modifying role entry.

Category:
Logging

Cause:

Action:

IAM-3010175
An error occurred while generating the {0}. Invalid values passed for attribute {1}.

Category:
Logging

Cause:

Action:

IAM-3010176
An error occurred while generating the {0}. No data passed for {1} generation.

Category:
Logging

Cause:

Action:

IAM-3010177
An error occurred while generating the {0}. The Policy {1} for {2} generation does not exist.

Category:
Logging

Cause:

Action:

IAM-3010178
An error occurred while generating the {0}. Cannot fetch the policy {1}.

Category:
Logging

Cause:

Action:

IAM-3010180
An error occurred while retrieving the User Entity Attributes for attribute length check in {0} generation.

Category:
Logging

Cause:

Action:

IAM-3010181
An error occurred while generating the {0}. Length of {1} exceeds the expected length {2}.

Category:
Logging

Cause:

Action:

IAM-3010182
An error occurred while generating the {0}. Length of one or more attributes exceeds the expected length.

Category:
Logging

Cause:

Action:

IAM-3010183
An error occurred while checking if a user already exists with the {0} generated. {0}

Category:
Logging

Cause:

Action:

IAM-3010185
An error occurred while generating the {0}. Please provide {1} as expected by {2}.

Category:
Logging

Cause:

Action:

IAM-3010186
An error occurred while generating the {0} because all of the generated names already exist.

Category:
Logging

Cause:

Action:

IAM-3010187
{0} generated in pre process handler - {0}.

Category:
Logging

Cause:

Action:

IAM-3010188
Unable to generate a {0} with the given data. Please specify a {1} manually or provide the required data as per generation policy.

Category:
Logging

Cause:

Action:

IAM-3010189
The container {0} already contains a user with the {1} {2}

Category:
Logging

Cause:

Action:

IAM-3010190
Either the RDN {0} of the user is being modified, or the user container is changed without referential integrity being enabled on target LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010191
An error occurred while verifying if {0} is unique.

Category:
Logging

Cause:

Action:

IAM-3010192
An error occurred while getting a connection to LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010194
An error occurred while getting the LDAP container rules.

Category:
Logging

Cause:

Action:

IAM-3010195
The user with key {0} will be deleted by scheduler once the automatically delete on date {1} is reached.

Category:
Logging

Cause:

Action:

IAM-3010196
The RDN {0} of the role is being modified, or the role container has changed, without referential integrity being enabled on target LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3010197
The user container is being changed to {0}, for which referential integrity needs to be enabled.

Category:
Logging

Cause:

Action:

IAM-3010198
Referential Integrity is not enabled in target LDAP system and hence the RDN {0} update will be ignored. Rest of the attributes will be updated.

Category:
Logging

Cause:

Action:

IAM-3010199
The {0} value {1} already exists or is reserved. Specify a different value for {2}

Category:
Logging

Cause:

Action:

IAM-3010200
The ldap connection was not found in the map, while trying to release it. The map contains {0} entries.

Category:
Logging

Cause:

Action:

IAM-3010201
LDAP create event failed : {0}

Category:
Logging

Cause:

Action:

IAM-3010202
An error occurred while performing LDAP operation for (key: {0}) - {1}

Category:
Logging

Cause:

Action:

IAM-3010203
Skipping reconciliation for the entry with DN : {0}. Error encountered is : {1}

Category:
Logging

Cause:

Action:

IAM-3010204
LDAP modify operation failed : {0}

Category:
Logging

Cause:

Action:

IAM-3010205
LDAP delete operation failed : {0}

Category:
Logging

Cause:

Action:

IAM-3011070
Adding user membership proceeded, but role {0} is not synchronized to the LDAP directory

Category:
Logging

Cause:

Action:

IAM-3011071
Deletion of user membership proceeded, but role {0} is not synchronized to the LDAP directory

Category:
Logging

Cause:

Action:

IAM-3011077
Deletion of user membership proceeded, but the role with LDAP DN {0} does not exist in the directory

Category:
Logging

Cause:

Action:

IAM-3011081
Deletion of role hierarchy proceeded, but the role with LDAP DN {0} does not exist in the directory

Category:
Logging

Cause:

Action:

IAM-3011200
Removing role membership, but a parallel relationship in LDAP could not be found

Category:
Logging

Cause:

Action:

IAM-3011201
Creating a role membership, but a parallel relationship in LDAP still exists

Category:
Logging

Cause:

Action:

IAM-3011202
Removing role grant, but a parallel relationship in LDAP could not be found

Category:
Logging

Cause:

Action:

IAM-3011203
Creating a role grant, but a parallel relationship in LDAP already exists

Category:
Logging

Cause:

Action:

IAM-3011204
Deleting a role in OIM, although the role could not be found in LDAP

Category:
Logging

Cause:

Action:

IAM-3012000
Exception occurred while parsing LDAP container DN : {0}

Category:
Logging

Cause:

Action:

IAM-3012001
Exception occurred while Entity validation : {0} - {1}

Category:
Logging

Cause:

Action:

IAM-3012002
Searching LDAP for container: {0}

Category:
Logging

Cause:

Action:

IAM-3012003
Found matching LDAP container : {0}

Category:
Logging

Cause:

Action:

IAM-3012004
An exception occurred while searching for LDAP container : {0} - {1}

Category:
Logging

Cause:

Action:

IAM-3012005
No LDAP container found with DN value: {0}

Category:
Logging

Cause:

Action:

IAM-3012006
Searching LDAP containers with RDN : {0}

Category:
Logging

Cause:

Action:

IAM-3012007
Found : {0}

Category:
Logging

Cause:

Action:

IAM-3012008
An exception occurred while searching LDAP containers with RDN : {0} - {1}

Category:
Logging

Cause:

Action:

IAM-3012009
No LDAP containers found with RDN : {0}

Category:
Logging

Cause:

Action:

IAM-3012010
Finding {0} entity LDAP container based on orchestration parameters and rules defined in LDAPContainerRules.xml

Category:
Logging

Cause:

Action:

IAM-3012011
Searching for Role with ID : {0}

Category:
Logging

Cause:

Action:

IAM-3012012
No Role found with the ID : {0}

Category:
Logging

Cause:

Action:

IAM-3012013
Found ...

Category:
Logging

Cause:

Action:

IAM-3012014
Exception in getting the Role details with Role Id : {0}

Category:
Logging

Cause:

Action:

IAM-3012015
Running validation for Role with ID : {0}

Category:
Logging

Cause:

Action:

IAM-3012016
Role DN : {0}

Category:
Logging

Cause:

Action:

IAM-3012017
Role GUID : {0}

Category:
Logging

Cause:

Action:

IAM-3012018
No Role exists in LDAP with specified GUID : {0}

Category:
Logging

Cause:

Action:

IAM-3012019
Error in retrieving Role details from LDAP with specified GUID : {0}

Category:
Logging

Cause:

Action:

IAM-3012020
Please refer to the Admin Servers logs for more details.

Category:
Logging

Cause:

Action:

IAM-3012021
No Role exists in LDAP with specified DN : {0}

Category:
Logging

Cause:

Action:

IAM-3012022
Error in retrieving Role details from LDAP with specified DN : {0}

Category:
Logging

Cause:

Action:

IAM-3012023
No Role exists in LDAP with specified DN : {0} or the specified GUID : {1}

Category:
Logging

Cause:

Action:

IAM-3012024
Role should be manually removed from Operational DB.

Category:
Logging

Cause:

Action:

IAM-3012025
An exception occurred while retrieving the Role in LDAP with GUID: {0} and DN {1}

Category:
Logging

Cause:

Action:

IAM-3012026
Validating Role DN ...

Category:
Logging

Cause:

Action:

IAM-3012027
Role DN - {0} in LDAP with specified GUID - {1} does not match the Role DN - {2} in OperationalDB.

Category:
Logging

Cause:

Action:

IAM-3012028
Validating Role GUID ...

Category:
Logging

Cause:

Action:

IAM-3012029
Role GUID - {0} in LDAP with specified DN - {1} does not match the Role GUID - {2} in OperationalDB.

Category:
Logging

Cause:

Action:

IAM-3012030
Searching Role with GUID : {0}

Category:
Logging

Cause:

Action:

IAM-3012031
Searching Role with DN : {0}

Category:
Logging

Cause:

Action:

IAM-3012032
Running validation for User with ID : {0}

Category:
Logging

Cause:

Action:

IAM-3012033
Searching for User with ID : {0}

Category:
Logging

Cause:

Action:

IAM-3012034
No User found for the given Id : {0}

Category:
Logging

Cause:

Action:

IAM-3012035
Exception in getting the User details for User Id : {0}

Category:
Logging

Cause:

Action:

IAM-3012036
Performing Objectclass validation ...

Category:
Logging

Cause:

Action:

IAM-3012037
Retrieved DN : {0} for Entity : {1}

Category:
Logging

Cause:

Action:

IAM-3012038
Retrieving Entity Metadata ...

Category:
Logging

Cause:

Action:

IAM-3012039
Retrieved Entity Objectclass ...

Category:
Logging

Cause:

Action:

IAM-3012040
An exception occurred in Objectclass validation. - {0}

Category:
Logging

Cause:

Action:

IAM-3012041
Validating Object Classes for DN : {0}

Category:
Logging

Cause:

Action:

IAM-3012042
Missing Objectclass : {0}

Category:
Logging

Cause:

Action:

IAM-3012043
Following Objectclasses are missing :

Category:
Logging

Cause:

Action:

IAM-3012044
Objectclass :

Category:
Logging

Cause:

Action:

IAM-3012045
Run the upgrade script to add the missing Object classes.

Category:
Logging

Cause:

Action:

IAM-3012046
Retrieving search base ...

Category:
Logging

Cause:

Action:

IAM-3012047
An exception occurred while retrieving the search base. - {0}

Category:
Logging

Cause:

Action:

IAM-3012048
Found Search base as : {0}

Category:
Logging

Cause:

Action:

IAM-3012049
Getting LDAP Connection ...

Category:
Logging

Cause:

Action:

IAM-3012050
Releasing LDAP connection ...

Category:
Logging

Cause:

Action:

IAM-3012051
An exception occurred while releasing the LDAP connection. - {0}

Category:
Logging

Cause:

Action:

IAM-3012052
Retrieving parameters for : {0}

Category:
Logging

Cause:

Action:

IAM-3012053
Error occurred while evaluating the exclude entity filter. - {0}

Category:
Logging

Cause:

Action:

IAM-3012054
Error occurred while retrieving the exclude entity filter. - {0}

Category:
Logging

Cause:

Action:

IAM-3012055
Orchestration parameter Map for membership is Null while evaluating the exclude entity filter.

Category:
Logging

Cause:

Action:

IAM-3012056
Userkey is Null while evaluating the exclude entity filter.

Category:
Logging

Cause:

Action:

IAM-3012057
Error occurred while retrieving the parameters for user identity {0} while evaluating the exclude entity filter. - {1}

Category:
Logging

Cause:

Action:

IAM-3012058
User Identity object is Null while evaluating the exclude entity filter.

Category:
Logging

Cause:

Action:

IAM-3012059
Orchestration parameter Map passed to evaluate is Null while evaluating the exclude entity filter.

Category:
Logging

Cause:

Action:

IAM-3012060
Error occurred while looking up user identity {0} while evaluating the exclude entity filter. - {1}

Category:
Logging

Cause:

Action:

IAM-3012061
An error occurred while retrieving the User Entity Attributes for evaluating the exclude entity filter.

Category:
Logging

Cause:

Action:

IAM-3012063
Exclude entity action is not configured in LDAPUser.xml file.

Category:
Logging

Cause:

Action:

IAM-3012067
LDAP Sync Full Reconciliation Scheduler job {0} is not currently Running. It has Failed.

Category:
Logging

Cause:

Action:

IAM-3012070
LDAP Sync Full Reconciliation Scheduler job {0} is not currently Running. SQLException has occurred.

Category:
Logging

Cause:

Action:

IAM-3012072
Changenumber: {0}. Datatypes expected {1}. Ignoring attribute {2} with datatype {3}.

Category:
Logging

Cause:

Action:

IAM-3012075
Could not process the change log number {0}.

Category:
Logging

Cause:

Action:

IAM-3012076
Either atomic full reconciliation job name {0} is invalid or not mapped.

Category:
Logging

Cause:

Action:

IAM-3012077
Few batch are still in progress for the job name {0}, parent job Id {1} after retry count {2}.

Category:
Logging

Cause:

Action:

IAM-3012078
Error occured while running atomic Full Reconciliation Scheduler job {0}

Category:
Logging

Cause:

Action:

IAM-3012079
Unbalanced parentheses in exclude entity filter rule - {0}.

Category:
Logging

Cause:

Action:

IAM-3012080
There is KM note created to address the issue of - "Invalid syntax of the provided cookie". Kindly refer to Doc ID 1599779.1 for the solution / workaround.

Category:
Logging

Cause:

Action:

IAM-3019900
Root Cause

Category:
Logging

Cause:

Action:

IAM-3020000
The entity {0} was not found!

Category:
Logging

Cause:

Action:

IAM-3020003
The attribute {0} does not exist!

Category:
Logging

Cause:

Action:

IAM-3020006
An exception occurred while retrieving the look-up values: {0}

Category:
Logging

Cause:

Action:

IAM-3020010
The look-up code {0} is invalid.

Category:
Logging

Cause:

Action:

IAM-3020016
Attribute creation failed due to an exception.

Category:
Logging

Cause:

Action:

IAM-3020019
The category {0} already exists.

Category:
Logging

Cause:

Action:

IAM-3020020
An error occurred while adding the category.

Category:
Logging

Cause:

Action:

IAM-3020021
Cannot delete a category with associated attributes: {0}.

Category:
Logging

Cause:

Action:

IAM-3020022
An error occurred while deleting the category.

Category:
Logging

Cause:

Action:

IAM-3020024
An error occurred while saving the attributes.

Category:
Logging

Cause:

Action:

IAM-3020025
Could not fetch the searchable attributes.

Category:
Logging

Cause:

Action:

IAM-3020026
An error occurred while fetching the LOV codes matching the pattern {0} : {1}.

Category:
Logging

Cause:

Action:

IAM-3020034
The category cannot be empty.

Category:
Logging

Cause:

Action:

IAM-3020036
The Default Value should be a number when the attribute Display Type is NUMBER.

Category:
Logging

Cause:

Action:

IAM-3020037
The Default Value should be either TRUE or FALSE CHECKBOX.

Category:
Logging

Cause:

Action:

IAM-3020038
Do not set the default value field when the attribute type is DATE.

Category:
Logging

Cause:

Action:

IAM-3020040
The existing LOV options and their respective descriptions cannot be modified.

Category:
Logging

Cause:

Action:

IAM-3020041
Invalid attribute size. Attribute size should be less than {0} and greater than or equal to {1}

Category:
Logging

Cause:

Action:

IAM-3020042
Invalid LOV column to save.

Category:
Logging

Cause:

Action:

IAM-3020043
Unable to get the length of DB column for attribute size validation.

Category:
Logging

Cause:

Action:

IAM-3020044
Error occurred while getting plug-in to execute query.

Category:
Logging

Cause:

Action:

IAM-3020046
Invalid LOV column to display.

Category:
Logging

Cause:

Action:

IAM-3020047
Error occurred while decoding Lookup query.

Category:
Logging

Cause:

Action:

IAM-3020049
An exception occurred while searching for encrypted attributes.

Category:
Logging

Cause:

Action:

IAM-3021000
You do not have permission to add an attribute.

Category:
Logging

Cause:

Action:

IAM-3021001
You do not have permission to update the attribute details.

Category:
Logging

Cause:

Action:

IAM-3021002
You do not have permission to delete an attribute.

Category:
Logging

Cause:

Action:

IAM-3021004
You do not have permission to add a category.

Category:
Logging

Cause:

Action:

IAM-3021005
You do not have permission to delete a category.

Category:
Logging

Cause:

Action:

IAM-3021006
You do not have permission to update the attribute details.

Category:
Logging

Cause:

Action:

IAM-3021007
You do not have permission to add derived attributes.

Category:
Logging

Cause:

Action:

IAM-3021008
You do not have permission to update search and advanced search attributes.

Category:
Logging

Cause:

Action:

IAM-3021009
You do not have permission to update search attributes.

Category:
Logging

Cause:

Action:

IAM-3021010
You do not have permission to update advanced search attributes.

Category:
Logging

Cause:

Action:

IAM-3021011
You do not have permission to update search result table attributes.

Category:
Logging

Cause:

Action:

IAM-3022030
Advanced search attributes cannot be empty.

Category:
Logging

Cause:

Action:

IAM-3022031
Simple search attributes cannot be empty.

Category:
Logging

Cause:

Action:

IAM-3022032
Search result attributes cannot be empty.

Category:
Logging

Cause:

Action:

IAM-3022033
The attributes configured for advanced search must be a subset of the attributes configured for simple search.

Category:
Logging

Cause:

Action:

IAM-3022034
The attributes configured for search result cannot contain encrypted attributes {0}.

Category:
Logging

Cause:

Action:

IAM-3022035
Cannot delete system attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3022036
A derived attribute cannot depend on itself {0}.

Category:
Logging

Cause:

Action:

IAM-3022037
Attribute name {0} cannot contain invalid characters {1}.

Category:
Logging

Cause:

Action:

IAM-3022038
Secret Attribute {0} should be encrypted.

Category:
Logging

Cause:

Action:

IAM-3022039
Encrypted Attribute {0} cannot have a default value.

Category:
Logging

Cause:

Action:

IAM-3022040
Encrypted Attribute {0} cannot be searchable.

Category:
Logging

Cause:

Action:

IAM-3022041
System controlled Attribute {0} cannot be Bulk updatable.

Category:
Logging

Cause:

Action:

IAM-3022042
Read only Attribute {0} cannot be Bulk updatable.

Category:
Logging

Cause:

Action:

IAM-3022043
Encrypted property cannot be modified for attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3022044
Property {0} cannot be modified for system attribute {1}.

Category:
Logging

Cause:

Action:

IAM-3022045
Validation failed for attribute {0}. LDAP attribute name is required.

Category:
Logging

Cause:

Action:

IAM-3023001
An error occurred while adding attribute {0}. Please check server logs for more information.

Category:
Logging

Cause:

Action:

IAM-3023002
An error occurred while modifying attribute {0}. Please check server logs for more information.

Category:
Logging

Cause:

Action:

IAM-3023003
An error occurred while deleting attribute {0}. Please check server logs for more information.

Category:
Logging

Cause:

Action:

IAM-3030004
E-mail attribute of user must be set if you want to send e-mail notification.

Category:
Logging

Cause:

Action:

IAM-3030005
Password value is null for entity {0}. Password History will not be updated.

Category:
Logging

Cause:

Action:

IAM-3030006
Password policy failed

Category:
Logging

Cause:

Action:

IAM-3030007
E-mail attribute of user or manager must be set if you want to send e-mail notification.

Category:
Logging

Cause:

Action:

IAM-3030008
Unable to find/read the system property XL.NotifyPasswordGenerationToOther

Category:
Logging

Cause:

Action:

IAM-3030010
No user found for the criteria {0}-{1}.

Category:
Logging

Cause:

Action:

IAM-3040000
The user has not defined the required number of questions.

Category:
Logging

Cause:

Action:

IAM-3040001
The User Challenge questions have not been set.

Category:
Logging

Cause:

Action:

IAM-3040002
Cannot set challenge questions for user due to validation errors.

Category:
Logging

Cause:

Action:

IAM-3040003
An exception was encountered while performing operation - {0}.

Category:
Logging

Cause:

Action:

IAM-3040004
Expired password for user - {0}

Category:
Logging

Cause:

Action:

IAM-3040005
Expired password operation failed due to validation errors.

Category:
Logging

Cause:

Action:

IAM-3040006
Validation failed for change password.

Category:
Logging

Cause:

Action:

IAM-3040007
The new password and confirm password are not the same.

Category:
Logging

Cause:

Action:

IAM-3040008
The user whose password is to be changed does not exist.

Category:
Logging

Cause:

Action:

IAM-3040009
The password change operation failed.

Category:
Logging

Cause:

Action:

IAM-3040010
The password for user {0} cannot be changed because the user has been deleted.

Category:
Logging

Cause:

Action:

IAM-3040011
The password change operation failed while searching for the user with GUID {0}

Category:
Logging

Cause:

Action:

IAM-3040012
The password change operation failed while validating old password.

Category:
Logging

Cause:

Action:

IAM-3040013
An error occurred while getting system property - {0}

Category:
Logging

Cause:

Action:

IAM-3040014
An error occurred while setting value in attribute - {0}

Category:
Logging

Cause:

Action:

IAM-3040015
An error occurred while searching for user - {0}

Category:
Logging

Cause:

Action:

IAM-3040016
An error occurred while updating the proxy for user - {0}

Category:
Logging

Cause:

Action:

IAM-3040017
An error occurred while parsing the date - {0}

Category:
Logging

Cause:

Action:

IAM-3040018
An error occurred while looking up user - {0}

Category:
Logging

Cause:

Action:

IAM-3040019
You do not have permission to modify details of user - {0}.

Category:
Logging

Cause:

Action:

IAM-3040020
An error occurred while getting user details.

Category:
Logging

Cause:

Action:

IAM-3040021
An error occurred while sending notification.

Category:
Logging

Cause:

Action:

IAM-3040022
You do not have permission to view details of user - {0}.

Category:
Logging

Cause:

Action:

IAM-3040023
You do not have permission to modify {0} attributes of user - {1}.

Category:
Logging

Cause:

Action:

IAM-3040024
The user {0} does not have access for operation {1}

Category:
Logging

Cause:

Action:

IAM-3040025
Cannot {0} the deleted user {1}

Category:
Logging

Cause:

Action:

IAM-3040026
The user with login {0} was not found.

Category:
Logging

Cause:

Action:

IAM-3040027
More than one user with the same login ID {0} found.

Category:
Logging

Cause:

Action:

IAM-3040028
The length of password should not be greater than {0}.

Category:
Logging

Cause:

Action:

IAM-3040029
Error fetching system property for notification - XL.NotifyUserCreateToOther. Using the property XL.NotifyPasswordGenerationToOther instead.

Category:
Logging

Cause:

Action:

IAM-3040030
No attribute is modified.

Category:
Logging

Cause:

Action:

IAM-3040031
The challenge answers could not be set because there were duplicate answers.

Category:
Logging

Cause:

Action:

IAM-3040032
Answer length is less than required minimum length

Category:
Logging

Cause:

Action:

IAM-3040033
Challenge questions provided are not defined in system.

Category:
Logging

Cause:

Action:

IAM-3040034
Password cannot be changed before {0}.

Category:
Logging

Cause:

Action:

IAM-3040035
Operation not supported.

Category:
Logging

Cause:

Action:

IAM-3042200
An error occurred while doing {0} operation on {1} entity with id {2}.

Category:
Logging

Cause:

Action:

IAM-3042201
An error occurred while doing search operation on {0} entity.

Category:
Logging

Cause:

Action:

IAM-3042202
Improper value for Attribute - {0}

Category:
Logging

Cause:

Action:

IAM-3042203
An error occurred while verifying the old user password during change password operation. : {0}.

Category:
Logging

Cause:

Action:

IAM-3042204
An error occurred while verifying the old user password during change password operation.

Category:
Logging

Cause:

Action:

IAM-3042205
An error occurred while obtaining the plug-in for {0} plug-in point : {1}

Category:
Logging

Cause:

Action:

IAM-3042206
The plug-in for {0} plug-in point is not found.

Category:
Logging

Cause:

Action:

IAM-3042207
An error occurred while getting the value for system property '"{0}"'.

Category:
Logging

Cause:

Action:

IAM-3042208
The password change operation failed - {0}

Category:
Logging

Cause:

Action:

IAM-3042209
The set challenge operation failed - {0}

Category:
Logging

Cause:

Action:

IAM-3042211
An error occurred while validating password minimum age during change password operation.

Category:
Logging

Cause:

Action:

IAM-3050002
An exception occurred while performing the operation.

Category:
Logging

Cause:

Action:

IAM-3050003
User modify parameters - {0}

Category:
Logging

Cause:

Action:

IAM-3050004
Searching for user login - {0}

Category:
Logging

Cause:

Action:

IAM-3050005
The user entity does not exist.

Category:
Logging

Cause:

Action:

IAM-3050006
The user with the user key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3050007
The user with the attribute {0} and value {1} already exists.

Category:
Logging

Cause:

Action:

IAM-3050008
Cannot perform the search with the given operations - {0}.

Category:
Logging

Cause:

Action:

IAM-3050009
Unknown attribute for entity user.

Category:
Logging

Cause:

Action:

IAM-3050010
An attribute being searched for is not searchable.

Category:
Logging

Cause:

Action:

IAM-3050011
The data type for a specified attribute is invalid.

Category:
Logging

Cause:

Action:

IAM-3050012
The data format for a specified attribute is invalid.

Category:
Logging

Cause:

Action:

IAM-3050013
Searching for users with the specified criteria.

Category:
Logging

Cause:

Action:

IAM-3050014
The user {0} does not have access for operation {1}.

Category:
Logging

Cause:

Action:

IAM-3050017
The user {0} was already deleted.

Category:
Logging

Cause:

Action:

IAM-3050021
The user with the key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3050022
Invalid number of users {0} entries returned for user ID {1}.

Category:
Logging

Cause:

Action:

IAM-3050023
The user with user login {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3050027
An exception occurred while validating user attributes.

Category:
Logging

Cause:

Action:

IAM-3050028
The mandatory attributes {0} were not provided.

Category:
Logging

Cause:

Action:

IAM-3050029
The user cannot be created due to validation errors.

Category:
Logging

Cause:

Action:

IAM-3050030
An exception occurred while performing the operation.

Category:
Logging

Cause:

Action:

IAM-3050031
The result of the {0} operation is {1}.

Category:
Logging

Cause:

Action:

IAM-3050033
Value for the mandatory attribute {0} was not provided.

Category:
Logging

Cause:

Action:

IAM-3050034
User deprovisioning date cannot be before start date.

Category:
Logging

Cause:

Action:

IAM-3050035
{0} should be less than {1}.

Category:
Logging

Cause:

Action:

IAM-3050036
{0} should be less than or equal to {1}.

Category:
Logging

Cause:

Action:

IAM-3050037
{0} should be greater than {1}.

Category:
Logging

Cause:

Action:

IAM-3050038
{0} should be greater than or equal to {1}.

Category:
Logging

Cause:

Action:

IAM-3050039
Cannot enable user {0} because the {1} is in the past.

Category:
Logging

Cause:

Action:

IAM-3050040
The user {0} will automatically get deleted after {1}.

Category:
Logging

Cause:

Action:

IAM-3050041
Failed while disabling user.

Category:
Logging

Cause:

Action:

IAM-3050042
Failed while enabling user.

Category:
Logging

Cause:

Action:

IAM-3050043
Operation not supported - {0}

Category:
Logging

Cause:

Action:

IAM-3050045
The password change operation failed.

Category:
Logging

Cause:

Action:

IAM-3050046
The users {0} successfully {1}.

Category:
Logging

Cause:

Action:

IAM-3050047
An exception occurred for the user in action handler.

Category:
Logging

Cause:

Action:

IAM-3050048
The validation failed exception for the following users -

Category:
Logging

Cause:

Action:

IAM-3050049
The users were successfully deleted.

Category:
Logging

Cause:

Action:

IAM-3050050
The user {0} cannot be a proxy for user {1} within specified period because user {2} is already a proxy for user {3} from {4} to {5}.

Category:
Logging

Cause:

Action:

IAM-3050051
The validation failed for this user.

Category:
Logging

Cause:

Action:

IAM-3050052
This attribute is not supported for the bulk modify operation.

Category:
Logging

Cause:

Action:

IAM-3050053
No attributes were configured for the bulk operation.

Category:
Logging

Cause:

Action:

IAM-3050054
Cannot enable the user {0} as his {1} is in future.

Category:
Logging

Cause:

Action:

IAM-3050056
The specified value {1} for attribute {0} is not one of the predefined values.

Category:
Logging

Cause:

Action:

IAM-3050058
Cannot assign the organization because it is not active.

Category:
Logging

Cause:

Action:

IAM-3050065
Cannot find the user being modified.

Category:
Logging

Cause:

Action:

IAM-3050066
The user {0} is out-of-box user. Cannot change the organization for an out-of-box user.

Category:
Logging

Cause:

Action:

IAM-3050067
An error occurred while getting group membership for the user {0}.

Category:
Logging

Cause:

Action:

IAM-3050068
The value {1} for attribute {0} is not valid. Please enter a valid value for attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3050069
Cannot modify the user details because user {0} was deleted.

Category:
Logging

Cause:

Action:

IAM-3050070
An error occurred while getting properties for user attribute {0} from configuration.

Category:
Logging

Cause:

Action:

IAM-3050071
An error occurred during the modify user preprocess stage.

Category:
Logging

Cause:

Action:

IAM-3050072
Special characters are not allowed for {0} attribute. Use only letters or numbers.

Category:
Logging

Cause:

Action:

IAM-3050073
The length of value for attribute {0} should not be greater than {1}.

Category:
Logging

Cause:

Action:

IAM-3050074
The operation initiator for delayed delete user operation is invalid - {0}.

Category:
Logging

Cause:

Action:

IAM-3050075
{0} {1} has already been reserved. Please provide another {2}.

Category:
Logging

Cause:

Action:

IAM-3050078
Cannot reserve user attribute {0} with value {1} in LDAP. Corresponding request ID is {2}.

Category:
Logging

Cause:

Action:

IAM-3050080
Cannot unreserve user attribute in LDAP for request ID {0}.

Category:
Logging

Cause:

Action:

IAM-3050082
An error occurred while unreserving User attribute and corresponding request ID is {0}.

Category:
Logging

Cause:

Action:

IAM-3050083
An error occurred while generating the Username. Please provide {0} as expected by {1}.

Category:
Logging

Cause:

Action:

IAM-3050084
An error occurred while generating the Username because all of the generated names already exist.

Category:
Logging

Cause:

Action:

IAM-3050087
An error occurred while searching for the user in {0}.

Category:
Logging

Cause:

Action:

IAM-3050089
The user {0} was already deleted and cannot be enabled.

Category:
Logging

Cause:

Action:

IAM-3050090
The user {0} was already deleted and cannot be disabled.

Category:
Logging

Cause:

Action:

IAM-3050091
Invalid data for MLS attribute(s) {0} and/or {1}.

Category:
Logging

Cause:

Action:

IAM-3050092
User name passed to pre process handler - {0}.

Category:
Logging

Cause:

Action:

IAM-3050093
User name generated in pre process handler - {0}.

Category:
Logging

Cause:

Action:

IAM-3050094
Unable to generate a username with the given data. Please specify a username manually or provide the required data as per policy.

Category:
Logging

Cause:

Action:

IAM-3050095
The attribute(s) {0} have invalid locale(s) {1}.

Category:
Logging

Cause:

Action:

IAM-3050096
An error occurred while generating the Username. Invalid values passed for attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3050097
An error occurred while generating the Username. No data passed for user name generation.

Category:
Logging

Cause:

Action:

IAM-3050098
An error occurred while generating the Username. The Policy {0} for user name generation does not exist.

Category:
Logging

Cause:

Action:

IAM-3050099
The user {0} was already deleted and cannot be locked.

Category:
Logging

Cause:

Action:

IAM-3050100
The user {0} was already deleted and cannot be unlocked.

Category:
Logging

Cause:

Action:

IAM-3050101
Modify User API cannot modify the password.

Category:
Logging

Cause:

Action:

IAM-3050102
The assigned user manager {0} is {1}.

Category:
Logging

Cause:

Action:

IAM-3050103
The manager with ID {0} being assigned to the user does not exist.

Category:
Logging

Cause:

Action:

IAM-3050104
An error occurred while searching for organization {0}.

Category:
Logging

Cause:

Action:

IAM-3050105
{0}

Category:
Logging

Cause:

Action:

IAM-3050108
An error occurred while populating the default MLS locale values for attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3050109
User with attribute {0}, value (1) does not exist.

Category:
Logging

Cause:

Action:

IAM-3050110
An error occurred while searching for the user.

Category:
Logging

Cause:

Action:

IAM-3050111
Cannot delete attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3050115
An error occurred while getting the list of available locales.

Category:
Logging

Cause:

Action:

IAM-3050116
An error occurred while generating the username. Length of {0} exceeds the expected length {1}.

Category:
Logging

Cause:

Action:

IAM-3050117
Cannot delete mandatory attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3050118
An error occurred while fetching organization hierarchy : {0}.

Category:
Logging

Cause:

Action:

IAM-3050119
Modify User API cannot change user status.

Category:
Logging

Cause:

Action:

IAM-3050120
To auto-generate the user password, the User or Manager must have a valid {0} for sending password notification.

Category:
Logging

Cause:

Action:

IAM-3050121
An error occurred while fetching organization type : {0}.

Category:
Logging

Cause:

Action:

IAM-3050122
An error occurred while retrieving the User Entity Attributes for attribute length check in username generation.

Category:
Logging

Cause:

Action:

IAM-3050123
An error occurred while reserving the user attribute. Cannot fetch the plugin for LDAP reservation.

Category:
Logging

Cause:

Action:

IAM-3050124
An error occurred while unreserving the user attribute. Cannot fetch the plugin for LDAP reservation.

Category:
Logging

Cause:

Action:

IAM-3050125
An error occurred while retrieving the value for system property {0}.

Category:
Logging

Cause:

Action:

IAM-3050126
An error occurred while generating the username. Cannot fetch the policy {0}.

Category:
Logging

Cause:

Action:

IAM-3050127
An error occurred in user name generation. Please provide either {0} or {1} and {2} for {3}.

Category:
Logging

Cause:

Action:

IAM-3050128
Cannot reserve user attribute {0} with value {1} in OIMDB. Corresponding request ID is {2}.

Category:
Logging

Cause:

Action:

IAM-3050129
Start date {0} should be later than current date.

Category:
Logging

Cause:

Action:

IAM-3050130
End date {0} should be later than current date.

Category:
Logging

Cause:

Action:

IAM-3050131
Start date {0} should be before End date {1}.

Category:
Logging

Cause:

Action:

IAM-3050132
User {0} cannot assign self proxy.

Category:
Logging

Cause:

Action:

IAM-3050133
An error occurred while fetching the Default Locale.

Category:
Logging

Cause:

Action:

IAM-3050134
System User {0} cannot be disabled.

Category:
Logging

Cause:

Action:

IAM-3050135
System User {0} cannot be deleted.

Category:
Logging

Cause:

Action:

IAM-3050136
User {0} cannot delete himself.

Category:
Logging

Cause:

Action:

IAM-3050137
User {0} cannot disable himself.

Category:
Logging

Cause:

Action:

IAM-3050138
User {0} cannot lock himself.

Category:
Logging

Cause:

Action:

IAM-3050140
The user {0} is already active and cannot be enabled.

Category:
Logging

Cause:

Action:

IAM-3050141
The user {0} is already disabled and cannot be disabled again.

Category:
Logging

Cause:

Action:

IAM-3050144
Compensate method called in pre-process handler of user operation {0} with process Id {1} and event Id {2}

Category:
Logging

Cause:

Action:

IAM-3050145
An error occurred while decrypting value for the attribute {0} for user with GUID {1}

Category:
Logging

Cause:

Action:

IAM-3050146
The base value for {0} should not be null for modify operation.

Category:
Logging

Cause:

Action:

IAM-3050149
An attribute being searched for is not searchable. {0}

Category:
Logging

Cause:

Action:

IAM-3050150
An error occurred while performing {0} operation. {1}

Category:
Logging

Cause:

Action:

IAM-3050152
An error occurred while reserving user attribute. {0}

Category:
Logging

Cause:

Action:

IAM-3050153
An error occurred while unreserving user attribute. {0}

Category:
Logging

Cause:

Action:

IAM-3050154
An error occurred while checking if a user already exists with the username generated. {0}

Category:
Logging

Cause:

Action:

IAM-3050155
An error occurred while checking if the username generated is already reserved. {0}

Category:
Logging

Cause:

Action:

IAM-3050156
An error occurred while modifying the following users : {0}

Category:
Logging

Cause:

Action:

IAM-3050157
Unknown attribute for entity user. {0}

Category:
Logging

Cause:

Action:

IAM-3050158
An error occurred while adding user proxy.

Category:
Logging

Cause:

Action:

IAM-3050159
An error occurred while updating user proxy.

Category:
Logging

Cause:

Action:

IAM-3050160
An error occurred while removing all user proxies.

Category:
Logging

Cause:

Action:

IAM-3050161
An error occurred while removing user proxy.

Category:
Logging

Cause:

Action:

IAM-3050162
An error occurred while performing modify user operation. {0}

Category:
Logging

Cause:

Action:

IAM-3050163
An error occurred while performing delete user operation. {0}

Category:
Logging

Cause:

Action:

IAM-3050164
An error occurred while performing disable user operation. {0}

Category:
Logging

Cause:

Action:

IAM-3050165
An error occurred while performing enable user operation. {0}

Category:
Logging

Cause:

Action:

IAM-3050166
An error occurred while performing lock user operation. {0}

Category:
Logging

Cause:

Action:

IAM-3050167
An error occurred while performing unlock user operation. {0}

Category:
Logging

Cause:

Action:

IAM-3050168
An error occurred while performing create user operation. {0}

Category:
Logging

Cause:

Action:

IAM-3050169
An error occurred while generating the username. Length of one or more attributes exceeds the expected length.

Category:
Logging

Cause:

Action:

IAM-3050171
Invalid attributes {0} are passed while updating proxy.

Category:
Logging

Cause:

Action:

IAM-3050172
Proxy start date and/or end date can not be null

Category:
Logging

Cause:

Action:

IAM-3050173
Proxy start date and/or Proxy user can not be modified for in-progress proxies

Category:
Logging

Cause:

Action:

IAM-3050174
No attributes are passed while updating proxy.

Category:
Logging

Cause:

Action:

IAM-3050192
An error occurred while getting a connection to LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3050193
An error occurred while reserving user attributes {0} with values {1} in LDAP. Corresponding request ID is {2}.

Category:
Logging

Cause:

Action:

IAM-3050194
A user cannot be his own manager.

Category:
Logging

Cause:

Action:

IAM-3050195
Tenant GUID is a mandatory attribute in Multi-Tenant Deployment.

Category:
Logging

Cause:

Action:

IAM-3050196
An error occurred while decrypting password.

Category:
Logging

Cause:

Action:

IAM-3050198
Could not retrieve the user id of the reserved user.

Category:
Logging

Cause:

Action:

IAM-3050199
{0} is not a valid DN.

Category:
Logging

Cause:

Action:

IAM-3050200
DN {0} is not within scope of parent DN {1}.

Category:
Logging

Cause:

Action:

IAM-3050202
User provisioning date cannot exist without an account start date.

Category:
Logging

Cause:

Action:

IAM-3050203
You do not have permission to unlock the user(s) with Id(s) {0} as the user(s) is locked by Administrator.

Category:
Logging

Cause:

Action:

IAM-3050205
An error occurred while reading OIA IT resource.

Category:
Logging

Cause:

Action:

IAM-3050206
An error occurred while calling OIA webservice.

Category:
Logging

Cause:

Action:

IAM-3050207
An error occurred while reading system property OIM.IsOIAIntegrationEnabled.

Category:
Logging

Cause:

Action:

IAM-3050208
OIA-ITRes is not configured.

Category:
Logging

Cause:

Action:

IAM-3050209
Operation failed due to invalid syntax for an attribute. {0}

Category:
Logging

Cause:

Action:

IAM-3050210
Configured Login attribute, {0}, must have a value.

Category:
Logging

Cause:

Action:

IAM-3051000
Failed to lookup the organization with org key {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-3051001
The organization modify operation failed for organization {0}.

Category:
Logging

Cause:

Action:

IAM-3051002
The organization delete operation failed for organization with key {0}.

Category:
Logging

Cause:

Action:

IAM-3051003
No such entity exists.

Category:
Logging

Cause:

Action:

IAM-3051005
The organization search operation failed.

Category:
Logging

Cause:

Action:

IAM-3051008
The organization with key(s) {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3051009
An exception occurred while performing the operation.

Category:
Logging

Cause:

Action:

IAM-3051010
The data type for a specified attribute is invalid.

Category:
Logging

Cause:

Action:

IAM-3051011
The data format for a specified attribute is invalid.

Category:
Logging

Cause:

Action:

IAM-3051012
The organization entity type is not defined.

Category:
Logging

Cause:

Action:

IAM-3051017
The {0} entity does not exist.

Category:
Logging

Cause:

Action:

IAM-3051018
The mandatory attribute {0} was not provided.

Category:
Logging

Cause:

Action:

IAM-3051019
The value of mandatory attribute {0} was not provided.

Category:
Logging

Cause:

Action:

IAM-3051020
The organization {0} already exists.

Category:
Logging

Cause:

Action:

IAM-3051022
The organization modify operation failed.

Category:
Logging

Cause:

Action:

IAM-3051023
An error occurred while searching for {0} organization.

Category:
Logging

Cause:

Action:

IAM-3051024
An error occurred while checking whether or not the new parent will create a cycle.

Category:
Logging

Cause:

Action:

IAM-3051025
Cannot modify the organization {0} because the parent organization creates a cyclic chain.

Category:
Logging

Cause:

Action:

IAM-3051026
The organization with key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3051027
An error occurred while searching for the organization with GUID {0}.

Category:
Logging

Cause:

Action:

IAM-3051028
The organization is already deleted.

Category:
Logging

Cause:

Action:

IAM-3051029
Cannot delete the organization because it has sub-organizations that have not been deleted.

Category:
Logging

Cause:

Action:

IAM-3051030
Cannot delete the organization because it has users that have not been deleted.

Category:
Logging

Cause:

Action:

IAM-3051031
Cannot delete the organization because it has sub-organizations and users that have not been deleted.

Category:
Logging

Cause:

Action:

IAM-3051032
Cannot disable the organization because it is already deleted.

Category:
Logging

Cause:

Action:

IAM-3051033
Cannot disable the organization because it has sub-organizations.

Category:
Logging

Cause:

Action:

IAM-3051034
Cannot disable the organization because it has users.

Category:
Logging

Cause:

Action:

IAM-3051035
Cannot disable the organization because it has sub-organizations and users.

Category:
Logging

Cause:

Action:

IAM-3051036
The organization disable operation failed.

Category:
Logging

Cause:

Action:

IAM-3051037
The organization enable operation failed.

Category:
Logging

Cause:

Action:

IAM-3051038
Cannot enable the organization because it has already been deleted.

Category:
Logging

Cause:

Action:

IAM-3051042
Cannot create the organization because the parent organization {0} has been deleted or disabled.

Category:
Logging

Cause:

Action:

IAM-3051043
Cannot modify the organization because the parent organization {0} has been deleted or disabled.

Category:
Logging

Cause:

Action:

IAM-3051044
You must provide an organization Key or Name to identify the organization for modification.

Category:
Logging

Cause:

Action:

IAM-3051046
You do not have permission to modify {0}.

Category:
Logging

Cause:

Action:

IAM-3051052
Password Policy with key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3051053
Cannot delete password policy for TOP Organization.

Category:
Logging

Cause:

Action:

IAM-3051054
The attribute {0} can not be modified for Top Organization.

Category:
Logging

Cause:

Action:

IAM-3051055
The delete operation failed for organization {0}

Category:
Logging

Cause:

Action:

IAM-3051057
Cannot delete the organization because it has a user membership rule set.

Category:
Logging

Cause:

Action:

IAM-3051058
Cannot disable the organization because it has a user membership rule set.

Category:
Logging

Cause:

Action:

IAM-3051100
Performing {0} operation on {1} entity having ID {2}.

Category:
Logging

Cause:

Action:

IAM-3051101
The enable operation on organization entity failed in action stage.

Category:
Logging

Cause:

Action:

IAM-3051102
The disable operation on organization entity failed in action stage.

Category:
Logging

Cause:

Action:

IAM-3051103
The create operation on user entity failed in action stage.

Category:
Logging

Cause:

Action:

IAM-3051106
USR_LOGIN cannot be reused because of missing configuration.

Category:
Logging

Cause:

Action:

IAM-3051112
The operation on Role entity failed in the audit stage.

Category:
Logging

Cause:

Action:

IAM-3051114
The operation on RoleUser relation failed in the audit stage.

Category:
Logging

Cause:

Action:

IAM-3051115
The operation on RoleRole relation failed in the audit stage.

Category:
Logging

Cause:

Action:

IAM-3051200
An error occurred while getting proxy details - {0}.

Category:
Logging

Cause:

Action:

IAM-3051201
An error occurred while getting available group details - {0}.

Category:
Logging

Cause:

Action:

IAM-3051202
An error occurred while parsing date - {0}.

Category:
Logging

Cause:

Action:

IAM-3051203
An error occurred while setting search configuration parameters - {0}.

Category:
Logging

Cause:

Action:

IAM-3051204
An error occurred while logging as admin for self-initiated create user operation - {0}.

Category:
Logging

Cause:

Action:

IAM-3051206
An error occurred while fetching the resource details for a user.

Category:
Logging

Cause:

Action:

IAM-3051207
An error occurred while fetching the resource details for a user - {0}.

Category:
Logging

Cause:

Action:

IAM-3051210
An error occurred while fetching role details of a user with key {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-3051211
An error occurred while fetching role details of a user with key {0}.

Category:
Logging

Cause:

Action:

IAM-3051212
An error occurred while searching for users - {0}.

Category:
Logging

Cause:

Action:

IAM-3051213
An error occurred while searching for user - {0}.

Category:
Logging

Cause:

Action:

IAM-3051214
An error occurred while searching for direct reports - {0}.

Category:
Logging

Cause:

Action:

IAM-3051221
An error occurred while getting additional user details - {0}.

Category:
Logging

Cause:

Action:

IAM-3051224
An error occurred while deleting the user(s).

Category:
Logging

Cause:

Action:

IAM-3051227
An error occurred while looking up a user with key {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-3051232
An error occurred while getting DB and UI attribute mapping - {0}.

Category:
Logging

Cause:

Action:

IAM-3051235
An error occurred while searching for the user attributes.

Category:
Logging

Cause:

Action:

IAM-3051236
Cannot perform the search user operation on unsearchable attributes.

Category:
Logging

Cause:

Action:

IAM-3051237
Cannot perform the search user operation on the following unsearchable attributes: {0}.

Category:
Logging

Cause:

Action:

IAM-3051238
An error has occurred while verifying the old password. : {0}.

Category:
Logging

Cause:

Action:

IAM-3051239
An error has occurred while verifying the old password.

Category:
Logging

Cause:

Action:

IAM-3051240
Either user login or user key should be provided to {0} plug-in.

Category:
Logging

Cause:

Action:

IAM-3051243
Operation not supported.

Category:
Logging

Cause:

Action:

IAM-3051244
Cannot delete the user {0} because it has subordinate users.

Category:
Logging

Cause:

Action:

IAM-3051245
The value {0} for sendNotificationTo parameter is not valid. Please enter valid value for sendNotificationTo parameter.

Category:
Logging

Cause:

Action:

IAM-3051300
An error occurred while fetching resources for the organization - {0}.

Category:
Logging

Cause:

Action:

IAM-3051301
An error occurred while fetching resources for the organization with key {0}.

Category:
Logging

Cause:

Action:

IAM-3051302
An error occurred while fetching administrative groups for the organization - {0}.

Category:
Logging

Cause:

Action:

IAM-3051303
An error occurred while fetching administrative groups for the organization with key {0}.

Category:
Logging

Cause:

Action:

IAM-3051304
An error occurred while searching for organization - {0}.

Category:
Logging

Cause:

Action:

IAM-3051311
An error occurred while fetching child organizations.

Category:
Logging

Cause:

Action:

IAM-3051312
An error occurred while preparing the search control parameters for organization search operation - {0}.

Category:
Logging

Cause:

Action:

IAM-3051319
Error. Found more than one organization for attribute name {0} and value {1}.

Category:
Logging

Cause:

Action:

IAM-3051320
Error. Cannot find an organization for attribute name {0} and value {1}.

Category:
Logging

Cause:

Action:

IAM-3051321
An error occurred while setting user membership rule.

Category:
Logging

Cause:

Action:

IAM-3051323
Available roles not supported in db mode.

Category:
Logging

Cause:

Action:

IAM-3051324
Deleting organization will result in the following orphaned published entities: {0}.

Category:
Logging

Cause:

Action:

IAM-3051325
An error occurred while trying to update dynamic org user/role membership rule and memberships for Organization {0} during post-process

Category:
Logging

Cause:

Action:

IAM-3051326
Dynamic rule attributes cannot be set during organization create or modify operations.

Category:
Logging

Cause:

Action:

IAM-3051327
Dynamic rule attribute has invalid rule syntax.

Category:
Logging

Cause:

Action:

IAM-3051328
An error occurred during updating dynamic user members of organization with key {0}.

Category:
Logging

Cause:

Action:

IAM-3051329
Cannot set membership rule on TOP organization

Category:
Logging

Cause:

Action:

IAM-3051330
In XE Dynamic User Role evaluation is always immediate.

Category:
Logging

Cause:

Action:

IAM-3051331
Cannot disable the Top organization

Category:
Logging

Cause:

Action:

IAM-3051332
Cannot delete the Top organization

Category:
Logging

Cause:

Action:

IAM-3051333
Invalid value for enforce password policy on reassignment : {0}

Category:
Logging

Cause:

Action:

IAM-3052000
The role with ID {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3052001
The role membership remove operation of user with key {0} failed for role with key {1}.

Category:
Logging

Cause:

Action:

IAM-3052002
Role parent cannot be a Dynamic role in LDAP Mode

Category:
Logging

Cause:

Action:

IAM-3052003
Dynamic Role cannot have Static members in LDAP Mode

Category:
Logging

Cause:

Action:

IAM-3052004
Dynamic Roles cannot have Catalog Attributes in LDAP Mode

Category:
Logging

Cause:

Action:

IAM-3052005
Static Roles cannot have a membership rule associated with it in LDAP Mode

Category:
Logging

Cause:

Action:

IAM-3052006
Invalid combination of attributes. A role cannot have both static & dynamic membership.

Category:
Logging

Cause:

Action:

IAM-3052200
Error occurred while doing lookup operation on {0} entity with ID {1}.

Category:
Logging

Cause:

Action:

IAM-3052201
Error occurred while doing search operation on {0} entity.

Category:
Logging

Cause:

Action:

IAM-3052202
No orchestration parameters for handler {0}.

Category:
Logging

Cause:

Action:

IAM-3052203
[ORCHPARAM] For handler {0}, key {1}, value in locale {2} is {3}.

Category:
Logging

Cause:

Action:

IAM-3052204
[ORCHPARAM] For handler {0}, key {1}, value type is {2} and value is {3}.

Category:
Logging

Cause:

Action:

IAM-3052205
An error occurred while performing Tenant Name lookup from Directory. Could not find Tenant entry with Tenant GUID = {0}.

Category:
Logging

Cause:

Action:

IAM-3052206
An unexpected error occurred while performing Tenant Name lookup from Directory. Error Details : {0}.

Category:
Logging

Cause:

Action:

IAM-3052207
An error occurred while performing Tenant Name lookup from Directory. Tenant entry found but it does not contain Tenant Name.

Category:
Logging

Cause:

Action:

IAM-3052208
OIM is configured in Multi Tenancy Environment.

Category:
Logging

Cause:

Action:

IAM-3052209
OIM is not configured in Multi Tenancy Environment.

Category:
Logging

Cause:

Action:

IAM-3053000
The start date processing scheduler search for users to be enabled automatically on reaching start date failed.

Category:
Logging

Cause:

Action:

IAM-3053001
The start date processing scheduler automatic enable operation failed.

Category:
Logging

Cause:

Action:

IAM-3053002
The end date processing scheduler search for users to be deleted or disabled failed.

Category:
Logging

Cause:

Action:

IAM-3053003
The end date processing scheduler automatic delete operation failed.

Category:
Logging

Cause:

Action:

IAM-3053004
The end date processing scheduler disable notification to be sent to {0} users manager {1} failed.

Category:
Logging

Cause:

Action:

IAM-3053005
The end date processing scheduler delete notification to be sent to {0} users manager {1} failed.

Category:
Logging

Cause:

Action:

IAM-3053006
Cannot send the end date processing scheduler notification because user {0} is still active despite a delete operation.

Category:
Logging

Cause:

Action:

IAM-3053007
The automatically unlock scheduler failed to search for users who are automatically locked and whose locking period is over.

Category:
Logging

Cause:

Action:

IAM-3053008
The automatically unlock processing scheduler automatic unlock operation failed.

Category:
Logging

Cause:

Action:

IAM-3053009
The delayed delete processing scheduler search for users to be deleted failed.

Category:
Logging

Cause:

Action:

IAM-3053010
The delayed delete processing scheduler delete operation failed.

Category:
Logging

Cause:

Action:

IAM-3053011
The user with key {0} will be deleted by scheduler once the automatically delete on date {1} is reached.

Category:
Logging

Cause:

Action:

IAM-3053012
The seed organization key scheduler search for users failed.

Category:
Logging

Cause:

Action:

IAM-3053013
An error occurred during user modify for entity id {0}: {1}.

Category:
Logging

Cause:

Action:

IAM-3053014
The seed organization key scheduler modify operation failed. Error: {0}

Category:
Logging

Cause:

Action:

IAM-3053032
Invalid search criteria provided.

Category:
Logging

Cause:

Action:

IAM-3053038
The user {0} does not have permissions on password policy operation {1}

Category:
Logging

Cause:

Action:

IAM-3053039
Error occurred while searching for password policies: {0}

Category:
Logging

Cause:

Action:

IAM-3053068
Error occurred while getting challenges

Category:
Logging

Cause:

Action:

IAM-3053069
Error while saving the password policy.

Category:
Logging

Cause:

Action:

IAM-3053070
Error while updating the password policy.

Category:
Logging

Cause:

Action:

IAM-3053071
Error while deleting the password policy.

Category:
Logging

Cause:

Action:

IAM-3053072
There is no password policy attached with Top organization

Category:
Logging

Cause:

Action:

IAM-3053077
Organization with Key as {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3053081
An error occured while decrypting password.

Category:
Logging

Cause:

Action:

IAM-3053082
An error occured - {0}.

Category:
Logging

Cause:

Action:

IAM-3053083
User Password validation against policy failed in IPF with error - {0}.

Category:
Logging

Cause:

Action:

IAM-3053084
Can not delete the password policy as it is attached to one or more Organizations.

Category:
Logging

Cause:

Action:

IAM-3053085
An error occured while localizaing challenge question {0}

Category:
Logging

Cause:

Action:

IAM-3053086
Pagination parameter STARTROW cannot be greater or equal to ENDROW. STARTROW = {0}, ENDROW = {1}.

Category:
Logging

Cause:

Action:

IAM-3054100
The logged-in user {0} does not have {1} permission on {2} entity.

Category:
Logging

Cause:

Action:

IAM-3054101
The logged-in user {0} does not have {1} permission on {2} {3} entity.

Category:
Logging

Cause:

Action:

IAM-3054105
The logged in user {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3054106
An error occurred while searching for the logged user {0}.

Category:
Logging

Cause:

Action:

IAM-3054107
You do not have permission to add a proxy for the user with user key {0}.

Category:
Logging

Cause:

Action:

IAM-3054108
You do not have permission to update a proxy for the user with user key {0}.

Category:
Logging

Cause:

Action:

IAM-3054109
You do not have permission to add a proxy for the user with user key {0}.

Category:
Logging

Cause:

Action:

IAM-3054110
You do not have permission to create a user.

Category:
Logging

Cause:

Action:

IAM-3054112
You do not have permission to modify the {0} attributes of the user with user Id {1}.

Category:
Logging

Cause:

Action:

IAM-3054113
You do not have permission to modify the user with user Id {0}.

Category:
Logging

Cause:

Action:

IAM-3054114
You do not have permission to delete the user(s) with user Id(s) {0}.

Category:
Logging

Cause:

Action:

IAM-3054115
You do not have permission to delete the user with user Id {0}.

Category:
Logging

Cause:

Action:

IAM-3054116
You do not have permission to disable the user with user Id {0}.

Category:
Logging

Cause:

Action:

IAM-3054117
You do not have permission to disable the user(s) with user Id(s) {0}.

Category:
Logging

Cause:

Action:

IAM-3054118
You do not have permission to enable the user with user Id {0}.

Category:
Logging

Cause:

Action:

IAM-3054119
You do not have permission to enable the user(s) with user Id(s) {0}.

Category:
Logging

Cause:

Action:

IAM-3054120
You do not have permission to lock the user with user Id {0}.

Category:
Logging

Cause:

Action:

IAM-3054121
You do not have permission to lock the user(s) with user Id(s) {0}.

Category:
Logging

Cause:

Action:

IAM-3054122
You do not have permission to unlock the user with user Id {0}.

Category:
Logging

Cause:

Action:

IAM-3054123
You do not have permission to unlock the user(s) with user Id(s) {0}.

Category:
Logging

Cause:

Action:

IAM-3054124
You do not have permission to change the password of the user with user Id {0}.

Category:
Logging

Cause:

Action:

IAM-3054125
You do not have permission to view details about the user.

Category:
Logging

Cause:

Action:

IAM-3054126
You do not have permission to search users.

Category:
Logging

Cause:

Action:

IAM-3054134
More than one user exists for the attribute name {0} with value {1}.

Category:
Logging

Cause:

Action:

IAM-3054135
No user found for the criteria {0}-{1}.

Category:
Logging

Cause:

Action:

IAM-3054136
You must provide a User Key or User Login to identity the user for modification.

Category:
Logging

Cause:

Action:

IAM-3054137
You do not have permission to view proxy details for the user with user key {0}.

Category:
Logging

Cause:

Action:

IAM-3054140
You do not have permission to search the following user attributes: {0}.

Category:
Logging

Cause:

Action:

IAM-3054141
You do not have permission to generate user name.

Category:
Logging

Cause:

Action:

IAM-3054142
You do not have permission to validate user name.

Category:
Logging

Cause:

Action:

IAM-3054143
You do not have permission to access the user name generation policies.

Category:
Logging

Cause:

Action:

IAM-3054144
You do not have permission to modify the user(s) with user key(s) {0} to set the manager with key {1}

Category:
Logging

Cause:

Action:

IAM-3054145
You do not have permission to modify the user(s) with user key(s) {0} to set the organization with key {1}

Category:
Logging

Cause:

Action:

IAM-3054146
User(s) can not be created in the organization with name {0}

Category:
Logging

Cause:

Action:

IAM-3056000
Create Parameters- {0}

Category:
Logging

Cause:

Action:

IAM-3056001
Submitted {0} request to Orchestration Engine for {1} with name {2}.

Category:
Logging

Cause:

Action:

IAM-3056002
An exception occurred while performing the operation.

Category:
Logging

Cause:

Action:

IAM-3056003
Modify Parameters- {0}

Category:
Logging

Cause:

Action:

IAM-3056004
Searching for Role- {0}

Category:
Logging

Cause:

Action:

IAM-3056005
The Entity Role does not exist.

Category:
Logging

Cause:

Action:

IAM-3056006
The Entity {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3056007
Unknown attribute for entity Role.

Category:
Logging

Cause:

Action:

IAM-3056008
Unknown attribute for entity Role - {0}.

Category:
Logging

Cause:

Action:

IAM-3056010
Unknown return attribute for entity Role - {0}.

Category:
Logging

Cause:

Action:

IAM-3056011
No return attributes for entity Role.

Category:
Logging

Cause:

Action:

IAM-3056012
An error occurred while searching for {0}s - {1}.

Category:
Logging

Cause:

Action:

IAM-3056013
Searching for {0} with the specified criteria.

Category:
Logging

Cause:

Action:

IAM-3056014
Cannot specify a value for attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3056015
Mandatory search criteria are empty for entity Role.

Category:
Logging

Cause:

Action:

IAM-3056029
Operation failed due to validation errors.

Category:
Logging

Cause:

Action:

IAM-3056030
An exception occurred while performing the operation.

Category:
Logging

Cause:

Action:

IAM-3056031
Result of the {0} operation is {1}.

Category:
Logging

Cause:

Action:

IAM-3056032
Role should only have one parent.

Category:
Logging

Cause:

Action:

IAM-3056033
An error occurred while loading the Role Manager queries.

Category:
Logging

Cause:

Action:

IAM-3056034
An error occurred while loading the cache.

Category:
Logging

Cause:

Action:

IAM-3056040
Successfully retrieved Role.xml from MDS.

Category:
Logging

Cause:

Action:

IAM-3056041
Cleaning UDF from Role.xml

Category:
Logging

Cause:

Action:

IAM-3056042
Proxy end date cannot be greater than proxy user {0} end date.

Category:
Logging

Cause:

Action:

IAM-3056043
Proxy start date cannot be less than proxy user {0} start date.

Category:
Logging

Cause:

Action:

IAM-3056044
You cannot assign a proxy to user {0} in Disabled/Disabled Until Start Date/Deleted status.

Category:
Logging

Cause:

Action:

IAM-3056045
User {0} cannot become a proxy in Disabled/Disabled Until Start Date/Deleted status.

Category:
Logging

Cause:

Action:

IAM-3056047
Cannot find a BPEL proxy rule for User {0}.

Category:
Logging

Cause:

Action:

IAM-3056049
User with key {0} or {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-3056050
An error occurred while validating whether user exists in database.

Category:
Logging

Cause:

Action:

IAM-3056051
Proxy key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3056052
An error occurred while validating whether proxy exists in database.

Category:
Logging

Cause:

Action:

IAM-3056054
User with key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3056059
An error occurred while updating Role.xml in MDS.

Category:
Logging

Cause:

Action:

IAM-3056060
An error occurred while validating whether proxy exists in database.{0}

Category:
Logging

Cause:

Action:

IAM-3056065
An error occurred while updating proxy with key {0}. Original user cannot be changed for a proxy.

Category:
Logging

Cause:

Action:

IAM-3056100
The operation on Role entity failed in the action stage.

Category:
Logging

Cause:

Action:

IAM-3056101
The operation on RoleCategory entity failed in the action stage.

Category:
Logging

Cause:

Action:

IAM-3056102
The operation on RoleUser relation failed in the action stage.

Category:
Logging

Cause:

Action:

IAM-3056103
The operation on RoleRole relation failed in the action stage.

Category:
Logging

Cause:

Action:

IAM-3056104
The operation on Role entity failed in the validation stage.

Category:
Logging

Cause:

Action:

IAM-3056105
The operation on RoleCategory entity failed in the validation stage.

Category:
Logging

Cause:

Action:

IAM-3056106
The operation on RoleUser relation failed in the validation stage.

Category:
Logging

Cause:

Action:

IAM-3056108
The operation on Role entity failed in the pre-processing stage.

Category:
Logging

Cause:

Action:

IAM-3056112
The operation on Role entity failed in the post-processing stage.

Category:
Logging

Cause:

Action:

IAM-3056114
The operation on RoleUser relation failed in the post-processing stage.

Category:
Logging

Cause:

Action:

IAM-3056116
Operation {0} is not supported.

Category:
Logging

Cause:

Action:

IAM-3056117
Another role with name {0} already exists in the same hierarchy.

Category:
Logging

Cause:

Action:

IAM-3056118
Cannot find role(s) with key(s) {0}.

Category:
Logging

Cause:

Action:

IAM-3056119
Cannot find user(s) with key(s) {0}.

Category:
Logging

Cause:

Action:

IAM-3056120
Cannot find role child with key {0}.

Category:
Logging

Cause:

Action:

IAM-3056121
The required orchestration parameters {0} and {1} are missing.

Category:
Logging

Cause:

Action:

IAM-3056122
Cyclical hierarchy with {0}.

Category:
Logging

Cause:

Action:

IAM-3056124
Attribute {0} is not supported for the bulk modify operation.

Category:
Logging

Cause:

Action:

IAM-3056125
Cannot find Role Category with {0} {1}.

Category:
Logging

Cause:

Action:

IAM-3056126
Cannot delete role {0} because it has existing relationships.

Category:
Logging

Cause:

Action:

IAM-3056127
Another role with name {0} already exists in the same namespace {1}.

Category:
Logging

Cause:

Action:

IAM-3056130
Cannot change the Role Category Name for- {0}.

Category:
Logging

Cause:

Action:

IAM-3056131
Cannot update or delete Role Category {0}.

Category:
Logging

Cause:

Action:

IAM-3056132
Another role with name {0} already exists.

Category:
Logging

Cause:

Action:

IAM-3056133
Role {0} is already granted to user {1}.

Category:
Logging

Cause:

Action:

IAM-3056134
Role {0} is NOT granted to user {1}.

Category:
Logging

Cause:

Action:

IAM-3056135
Role {0} is already parent of role {1}.

Category:
Logging

Cause:

Action:

IAM-3056136
Role {0} is NOT a parent of role {1}.

Category:
Logging

Cause:

Action:

IAM-3056137
Cannot revoke role grant to role {0}.

Category:
Logging

Cause:

Action:

IAM-3056138
Another role category with name {0} already exists.

Category:
Logging

Cause:

Action:

IAM-3056139
Cannot change the name of a Oracle Identity Manager system role.

Category:
Logging

Cause:

Action:

IAM-3056140
Cannot find a role for the criteria: {0}-{1}.

Category:
Logging

Cause:

Action:

IAM-3056141
More than one role exists for the attribute name {0} with value {1}.

Category:
Logging

Cause:

Action:

IAM-3056142
Cannot grant the role {0} to disabled or deleted user(s) {1}.

Category:
Logging

Cause:

Action:

IAM-3056143
Cannot find a role category for the criteria: {0}-{1}.

Category:
Logging

Cause:

Action:

IAM-3056144
More than one role category exists for the attribute name {0} with value {1}.

Category:
Logging

Cause:

Action:

IAM-3056145
Cannot find a user for the criteria: {0}-{1}.

Category:
Logging

Cause:

Action:

IAM-3056146
More than one user exists for the attribute name {0} with value {1}.

Category:
Logging

Cause:

Action:

IAM-3056147
Cannot delete Role Category {0} because it has some associated roles.

Category:
Logging

Cause:

Action:

IAM-3056148
{0} is a System Attribute and cannot be set through API.

Category:
Logging

Cause:

Action:

IAM-3056149
The base value for Role Display Name should not be null for a modify operation.

Category:
Logging

Cause:

Action:

IAM-3056150
Cannot change the base value for the display name of an Oracle Identity Manager system role.

Category:
Logging

Cause:

Action:

IAM-3056151
Cannot delete an Oracle Identity Manager system role.

Category:
Logging

Cause:

Action:

IAM-3056152
Cannot assign {0} to {1} user.

Category:
Logging

Cause:

Action:

IAM-3056153
Role does not exist.

Category:
Logging

Cause:

Action:

IAM-3056155
Required attributes cannot be null or empty for user create operation.

Category:
Logging

Cause:

Action:

IAM-3056156
Cannot accept multiple values for attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3056157
Append or Delete on multi valued attribute {0} is not supported in bulk modify operation. Only replace all is supported.

Category:
Logging

Cause:

Action:

IAM-3056158
Cannot accept multiple values for attribute {0} in delta mode for user create operation.

Category:
Logging

Cause:

Action:

IAM-3056159
The value {0} provided for the attribute {1} is not of the required type {2}.

Category:
Logging

Cause:

Action:

IAM-3056160
{0} request cannot set or change attribute {1}, since it is not defined in the corresponding data set.

Category:
Logging

Cause:

Action:

IAM-3056161
Revoke of role with id {0} for user-id {1} failed.

Category:
Logging

Cause:

Action:

IAM-3056164
The operation on PendingRoleUser relation failed in the action stage.

Category:
Logging

Cause:

Action:

IAM-3056167
Role {0} is already granted to user {1} and is pending for start date to reach.

Category:
Logging

Cause:

Action:

IAM-3056169
Invalid End Date {0} specified. It should be greater than current time {1}.

Category:
Logging

Cause:

Action:

IAM-3056170
Start Date {0} and End Date {1} specified is not valid combination.

Category:
Logging

Cause:

Action:

IAM-3056171
The role {0} was created, but there were some errors while performing the role post operations - {1}

Category:
Logging

Cause:

Action:

IAM-3056172
Error while deserializing attribute {0} with value {1}

Category:
Logging

Cause:

Action:

IAM-3056173
Error while removing access policies from role {0} - {1}

Category:
Logging

Cause:

Action:

IAM-3056174
Assignment of entity publications to role {0} failed with error: {1}

Category:
Logging

Cause:

Action:

IAM-3056175
Assignment of access policy {0} failed for role with key {1}, with error: {2}

Category:
Logging

Cause:

Action:

IAM-3056176
Assignment of user membership rule {0} failed for role with key {1}, with error: {2}

Category:
Logging

Cause:

Action:

IAM-3056177
Error while fetching the access policy with key {0} - {1}

Category:
Logging

Cause:

Action:

IAM-3056178
The access policy with key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3056179
Error while searching for organizations - {0}

Category:
Logging

Cause:

Action:

IAM-3056180
{0} out of the {1} organizations do not exist - {2}

Category:
Logging

Cause:

Action:

IAM-3056181
{0} is an invalid key for role {1}. Access policy Map only accepts keys ADD and DELETE.

Category:
Logging

Cause:

Action:

IAM-3056182
{0} is an invalid key for role {1}. Entity publications Map only accepts keys ADD and DELETE.

Category:
Logging

Cause:

Action:

IAM-3056183
Unrecognized data type for access policy - {0}. Expected List<String> or Map<String, String>

Category:
Logging

Cause:

Action:

IAM-3056184
Unrecognized data type for entity publications - {0}. Expected List<EntityPublication> or Map<String, EntityPublication>

Category:
Logging

Cause:

Action:

IAM-3056185
Failed to unassign access policy {0} for role with key {1}, with error: {2}

Category:
Logging

Cause:

Action:

IAM-3056186
Failed to delete entity publications for role {0} with error: {1}

Category:
Logging

Cause:

Action:

IAM-3056187
An error occurred while granting role with key {0} to user with key {1} - {2}

Category:
Logging

Cause:

Action:

IAM-3056188
An error occurred while revoking role with key {0} from user with key {1} - {2}

Category:
Logging

Cause:

Action:

IAM-3056189
There were some errors while executing the Pending Role Grants schedule job - {0}

Category:
Logging

Cause:

Action:

IAM-3056190
Error occurred while updating the request status to {0} for request key {1}. Error: {2}

Category:
Logging

Cause:

Action:

IAM-3056192
Unable to update the request status and/or failure reason for request key {0} due to error: {1}

Category:
Logging

Cause:

Action:

IAM-3056193
The Approver User {0} was not found.

Category:
Logging

Cause:

Action:

IAM-3056194
The Certifier User {0} was not found.

Category:
Logging

Cause:

Action:

IAM-3056195
The FulFillment User {0} was not found.

Category:
Logging

Cause:

Action:

IAM-3056196
The Approver Role {0} was not found.

Category:
Logging

Cause:

Action:

IAM-3056197
The Certifier Role {0} was not found.

Category:
Logging

Cause:

Action:

IAM-3056198
The FulFillment Role {0} was not found.

Category:
Logging

Cause:

Action:

IAM-3056200
The following role parents were not found: {0}

Category:
Logging

Cause:

Action:

IAM-3056201
Request successfully submitted for role membership grant with request ID {0}

Category:
Logging

Cause:

Action:

IAM-3056202
Start Date {0} can not be updated as the role {1} is already granted to the user {2}.

Category:
Logging

Cause:

Action:

IAM-3056203
End Date {0} can not be updated to a date in the past.

Category:
Logging

Cause:

Action:

IAM-3056204
Request successfully submitted for role membership revoke with request ID {0}

Category:
Logging

Cause:

Action:

IAM-3056205
An exception occurred while granting role {0} to users {1}: {2}

Category:
Logging

Cause:

Action:

IAM-3056206
An exception occurred while revoking role {0} from users {1}: {2}

Category:
Logging

Cause:

Action:

IAM-3056207
An exception occurred while trying to update pending grant for role {0} and users {1}: {2}

Category:
Logging

Cause:

Action:

IAM-3056208
Can not modify role grant as it doesn''t exist! User {0} and role {1}

Category:
Logging

Cause:

Action:

IAM-3056209
Update of entity publications for role {0} failed with error: {1}

Category:
Logging

Cause:

Action:

IAM-3056210
An error occurred while getting similar roles for role {0}: {1}

Category:
Logging

Cause:

Action:

IAM-3056211
Can not have the start date {0} in the past.

Category:
Logging

Cause:

Action:

IAM-3056212
Audit error: Failed to audit operation {0} for entity {1} {2} due to {3}

Category:
Logging

Cause:

Action:

IAM-3056216
Role was created successfully, but not all memberships were granted: {0}

Category:
Logging

Cause:

Action:

IAM-3056217
Role was updated successfully, but not all memberships were updated: {0}

Category:
Logging

Cause:

Action:

IAM-3056218
Role Consolidation matches {0} roles

Category:
Logging

Cause:

Action:

IAM-3056219
Start Date for pending grant {0}:{1} can not be nullified. Please set to today''s date to have the role granted today.

Category:
Logging

Cause:

Action:

IAM-3056224
Role cannot be granted. User with ID {0} has been deleted.

Category:
Logging

Cause:

Action:

IAM-3057001
An exception occurred while validating add proxy operation.

Category:
Logging

Cause:

Action:

IAM-3057002
An exception occurred while validating update proxy operation.

Category:
Logging

Cause:

Action:

IAM-3057004
Proxy conflicts with already existing proxy for users :{0}.

Category:
Logging

Cause:

Action:

IAM-3057005
Invalid Proxy Id.

Category:
Logging

Cause:

Action:

IAM-3057006
All proxy related operations are forbidden because the OIM instance is configured to not to use SOA.

Category:
Logging

Cause:

Action:

IAM-3058000
Cannot initialize the Rule Engine - {0}.

Category:
Logging

Cause:

Action:

IAM-3058001
Un-supported relationship type.

Category:
Logging

Cause:

Action:

IAM-3058002
Entity ID must be set.

Category:
Logging

Cause:

Action:

IAM-3058102
Error occurred while calculating the dynamic organization membership of user - {0}.

Category:
Logging

Cause:

Action:

IAM-3058103
Attribute does not exist - {0}.

Category:
Logging

Cause:

Action:

IAM-3058104
Attribute "{0}" is marked as not searchable in the entity definition, make sure it has an index.

Category:
Logging

Cause:

Action:

IAM-3058105
Error while removing org-user memberships on deletion of user - {0}.

Category:
Logging

Cause:

Action:

IAM-3058106
Error while removing role-user memberships on deletion of user - {0}.

Category:
Logging

Cause:

Action:

IAM-3058107
Error while granting the roles to the user as per the role relation-ship rule.

Category:
Logging

Cause:

Action:

IAM-3058108
Error while granting the roles to the users as per the role relation-ship rule.

Category:
Logging

Cause:

Action:

IAM-3058109
Error while retrieving IT resource parameters

Category:
Logging

Cause:

Action:

IAM-3058110
Cannot assign {0} to {1} user as they are not from same tenant.

Category:
Logging

Cause:

Action:

IAM-3058111
Error occurred while auto assigning admin role memberships to user with key {0}.

Category:
Logging

Cause:

Action:

IAM-3058112
Error occurred while fetching challenges for user {0}

Category:
Logging

Cause:

Action:

IAM-3058113
Cannot set challenge questions for user due to validation errors.

Category:
Logging

Cause:

Action:

IAM-3058114
Error occurred while setting challenges for user by admin

Category:
Logging

Cause:

Action:

IAM-3058115
Username generation for a chosen User Name Policy is effecting user creation performance, consider providing unique to User Name Policy attributes or switch to another policy.

Category:
Logging

Cause:

Action:

IAM-3059000
Error while searching for user with login id {0}. Corresponding error message is: {1}.

Category:
Logging

Cause:

Action:

IAM-3059001
You do not have rights to search and view on one or more attributes.

Category:
Logging

Cause:

Action:

IAM-3071001
Cannot interpret the request due to malformed request data.

Category:
Logging

Cause:

Action:

IAM-3071004
{0} with guid {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-3071006
The requested mode of execution is not supported.

Category:
Logging

Cause:

Action:

IAM-3071015
An exception occurred while converting request data to a PSO Identity object.

Category:
Logging

Cause:

Action:

IAM-3071016
An exception occurred while adding request data in the response.

Category:
Logging

Cause:

Action:

IAM-3071017
An exception occurred while getting the list of targets.

Category:
Logging

Cause:

Action:

IAM-3071018
An exception occurred while fetching the callback errors.

Category:
Logging

Cause:

Action:

IAM-3071019
The request was successful, but the callback handler failed.

Category:
Logging

Cause:

Action:

IAM-3071020
An error occurred while preparing operational data for the request.

Category:
Logging

Cause:

Action:

IAM-3071021
Found Capability Data, but it was empty.

Category:
Logging

Cause:

Action:

IAM-3071022
The attribute {0} is not multi-language enabled in OIM. Only the value {1} will be saved.

Category:
Logging

Cause:

Action:

IAM-3071023
An error occurred while determining the list of invalid MLS attributes.

Category:
Logging

Cause:

Action:

IAM-3071024
Role Category Name {0} does not exist

Category:
Logging

Cause:

Action:

IAM-3071025
An exception was encountered while performing the role category search operation.

Category:
Logging

Cause:

Action:

IAM-3071026
Password cannot be empty or null.

Category:
Logging

Cause:

Action:

IAM-3071027
The {0} is not specified or not in proper format. Hence ignored.

Category:
Logging

Cause:

Action:

IAM-3071029
The requesterGUID (user key/userid/guid) {0} passed in the request doesn"t exist in OIM.

Category:
Logging

Cause:

Action:

IAM-3072001
Request contains incorrect data.

Category:
Logging

Cause:

Action:

IAM-3072002
Request data contains incorrect beneficiaries information.

Category:
Logging

Cause:

Action:

IAM-3072003
Request data contains incorrect identity information.

Category:
Logging

Cause:

Action:

IAM-3072004
Request data contains incorrect role information.

Category:
Logging

Cause:

Action:

IAM-3072005
Request data contains incorrect role membership information.

Category:
Logging

Cause:

Action:

IAM-3072006
Request contains multiple values for parent role.

Category:
Logging

Cause:

Action:

IAM-3072007
Request contains unsupported data for this operation - {0}.

Category:
Logging

Cause:

Action:

IAM-3072008
Request ID cannot be null or empty.

Category:
Logging

Cause:

Action:

IAM-3072009
Requestor failed authorization checks to create request

Category:
Logging

Cause:

Action:

IAM-3072010
Requestor is not authorized to check status of users

Category:
Logging

Cause:

Action:

IAM-3072011
Requestor is not authorized to raise SPML requests since it does not have the SPML Administrator admin role.

Category:
Logging

Cause:

Action:

IAM-3073001
Request data contains an invalid identity modification operation.

Category:
Logging

Cause:

Action:

IAM-3073003
The value {1} for attribute {0} is not valid. Please enter valid value for attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3073004
No default Organization found to assign to the user. Please verify if logged-in user has sufficient permissions to view default organization " Xellerate Users".

Category:
Logging

Cause:

Action:

IAM-3074001
Request data contains an invalid identity PSO identifier.

Category:
Logging

Cause:

Action:

IAM-3074002
Request data contains an invalid role PSO identifier.

Category:
Logging

Cause:

Action:

IAM-3074004
Request data contains an invalid role membership modification operation.

Category:
Logging

Cause:

Action:

IAM-3074005
Request data contains an invalid role membership modification count.

Category:
Logging

Cause:

Action:

IAM-3074006
Request data identity PSO identifier - {0}

Category:
Logging

Cause:

Action:

IAM-3074007
Request data role PSO identifier - {0}

Category:
Logging

Cause:

Action:

IAM-3074008
Request data target identity PSO identifier - {0}

Category:
Logging

Cause:

Action:

IAM-3074009
Request data target role PSO identifier - {0}

Category:
Logging

Cause:

Action:

IAM-3074010
Request is missing compulsory information - {0}.

Category:
Logging

Cause:

Action:

IAM-3074011
Request contains an unsupported capabilityURI - {0}.

Category:
Logging

Cause:

Action:

IAM-3074012
Request contains an invalid Id/Guid identifier - {0}.

Category:
Logging

Cause:

Action:

IAM-3074013
Filtered duplicate Role Id/Guid identifier(s) - {0}.

Category:
Logging

Cause:

Action:

IAM-3074014
Request contains an invalid value for Parent Role.

Category:
Logging

Cause:

Action:

IAM-3074015
Request does not contain Role capability data.

Category:
Logging

Cause:

Action:

IAM-3074016
Cannot assign role(s) to, or revoke role(s) from, disabled/deleted users.

Category:
Logging

Cause:

Action:

IAM-3074017
Filtered unassigned Roles for revoke operation - {0}.

Category:
Logging

Cause:

Action:

IAM-3074018
Filtered already assigned Roles for grant operation - {0}.

Category:
Logging

Cause:

Action:

IAM-3074019
No valid roles passed for grant/revoke operation.

Category:
Logging

Cause:

Action:

IAM-3075001
Cannot process the request due to an internal server error.

Category:
Logging

Cause:

Action:

IAM-3076001
Mandatory attributes are missing in the request data: {0}.

Category:
Logging

Cause:

Action:

IAM-3076002
User with {0} = {1} already exists.

Category:
Logging

Cause:

Action:

IAM-3076003
Invalid locale code {1} found for MLS attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3076004
The entity "User" does not exist.

Category:
Logging

Cause:

Action:

IAM-3076005
An error occurred while getting user attribute details for attribute {0} from configuration.

Category:
Logging

Cause:

Action:

IAM-3076006
Unable to generate a username with the given data. Please specify a username manually or provide the required data as per policy.

Category:
Logging

Cause:

Action:

IAM-3076007
Error in username generation.

Category:
Logging

Cause:

Action:

IAM-3076008
Error in random password generation.

Category:
Logging

Cause:

Action:

IAM-3076009
Invalid data for MLS attribute(s) {0} and/or {1}.

Category:
Logging

Cause:

Action:

IAM-3076010
An error occurred while searching for organization {0}.

Category:
Logging

Cause:

Action:

IAM-3076011
The organization assigned to user cannot be {0}.

Category:
Logging

Cause:

Action:

IAM-3076012
{0} {1} has already been reserved. Please provide another {2}.

Category:
Logging

Cause:

Action:

IAM-3076013
The manager being assigned to the user does not exist.

Category:
Logging

Cause:

Action:

IAM-3076014
An exception occurred while validating user attributes.

Category:
Logging

Cause:

Action:

IAM-3076015
{0} should be greater than or equal to {1}.

Category:
Logging

Cause:

Action:

IAM-3076016
{0} should be greater than {1}.

Category:
Logging

Cause:

Action:

IAM-3076017
{0} should be less than or equal to {1}.

Category:
Logging

Cause:

Action:

IAM-3076018
{0} should be less than {1}.

Category:
Logging

Cause:

Action:

IAM-3076020
The specified value "{1}" for attribute {0} is not one of the predefined values.

Category:
Logging

Cause:

Action:

IAM-3076021
The mandatory attributes {0} were not provided.

Category:
Logging

Cause:

Action:

IAM-3076022
A value was not provided for mandatory attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3076023
Special Characters are not allowed for {0} attribute. Use only Letters or Numbers.

Category:
Logging

Cause:

Action:

IAM-3076024
Length of value for the attribute {0} should be not be greater than {1}.

Category:
Logging

Cause:

Action:

IAM-3076025
The create operation on user entity failed in action stage.

Category:
Logging

Cause:

Action:

IAM-3076026
An error occurred while populating default MLS locale values for attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3076027
User with attribute {0}, value (1) does not exist

Category:
Logging

Cause:

Action:

IAM-3076028
An error occurred during the modify user preprocess stage.

Category:
Logging

Cause:

Action:

IAM-3076029
An error occurred while searching for the user.

Category:
Logging

Cause:

Action:

IAM-3076030
The user {0} was deleted. Cannot modify the user.

Category:
Logging

Cause:

Action:

IAM-3076031
Cannot modify the user password using the modify operation.

Category:
Logging

Cause:

Action:

IAM-3076032
User with attribute {0} - value {1} already exists.

Category:
Logging

Cause:

Action:

IAM-3076033
User {0} is a system user. The organization of a system user cannot be changed.

Category:
Logging

Cause:

Action:

IAM-3076034
Cannot assign an organization that is {0}.

Category:
Logging

Cause:

Action:

IAM-3076035
An error occurred while deleting the user.

Category:
Logging

Cause:

Action:

IAM-3076036
User with the attribute {0}, value {1} already exists.

Category:
Logging

Cause:

Action:

IAM-3076038
User {0} will automatically get deleted after {1}.

Category:
Logging

Cause:

Action:

IAM-3076039
Operation not supported - {0}

Category:
Logging

Cause:

Action:

IAM-3076040
Failed while enabling user

Category:
Logging

Cause:

Action:

IAM-3076041
User {0} cannot be enabled because user"s {1} is in the future.

Category:
Logging

Cause:

Action:

IAM-3076042
User {0} is already deleted and cannot be enabled.

Category:
Logging

Cause:

Action:

IAM-3076043
User {0} cannot be enabled because the {1} is in past.

Category:
Logging

Cause:

Action:

IAM-3076044
The user {0} is already deleted and cannot be disabled.

Category:
Logging

Cause:

Action:

IAM-3076045
Role {0} cannot be deleted because it has existing relationships.

Category:
Logging

Cause:

Action:

IAM-3076046
An error occurred while finding user for corresponding {0} "{1}".

Category:
Logging

Cause:

Action:

IAM-3076047
User does not exist.

Category:
Logging

Cause:

Action:

IAM-3076048
{0} {1} already exists.

Category:
Logging

Cause:

Action:

IAM-3076049
User {0} is already {1}.

Category:
Logging

Cause:

Action:

IAM-3076050
An error occurred while finding roles assigned to user for corresponding {0} "{1}".

Category:
Logging

Cause:

Action:

IAM-3076051
{0} {1} is already assigned to user for corresponding {2} "{3}"

Category:
Logging

Cause:

Action:

IAM-3076052
{0} {1} is not assigned to user for corresponding {2} "{3}"

Category:
Logging

Cause:

Action:

IAM-3076053
An error occurred while finding user for corresponding {0} "{1}"

Category:
Logging

Cause:

Action:

IAM-3076054
{0} {1} has already been reserved. Please provide another {2}.

Category:
Logging

Cause:

Action:

IAM-3076055
An error occurred while searching lookup values defined for lookup-code {0}.

Category:
Logging

Cause:

Action:

IAM-3076056
An error occurred while getting IT Resource Instances defined for IT Resource Type {0}.

Category:
Logging

Cause:

Action:

IAM-3076057
An error occurred while generating the username.

Category:
Logging

Cause:

Action:

IAM-3076058
An error occurred while generating a random password.

Category:
Logging

Cause:

Action:

IAM-3076059
Password Policy Failed - a blank password is not allowed.

Category:
Logging

Cause:

Action:

IAM-3076060
Password Policy Failed - {0}

Category:
Logging

Cause:

Action:

IAM-3076061
Request Data is invalid. Length of the attribute value {0} is greater than maximum allowed length {1}.

Category:
Logging

Cause:

Action:

IAM-3076062
An error occurred while getting the list of available locales.

Category:
Logging

Cause:

Action:

IAM-3076063
The attribute(s) {0} have invalid MLS locale(s) {1}.

Category:
Logging

Cause:

Action:

IAM-3076064
Attribute {0} is not supported for this operation or may be invalid.

Category:
Logging

Cause:

Action:

IAM-3076065
{0} {1} are already assigned to user for corresponding {2} "{3}".

Category:
Logging

Cause:

Action:

IAM-3076066
{0} {1} are not assigned to user for corresponding {2} "{3}".

Category:
Logging

Cause:

Action:

IAM-3076067
For {0} to be auto-generated, either {1} or {2} is required for sending notification.

Category:
Logging

Cause:

Action:

IAM-3076068
No request found with specified request ID.

Category:
Logging

Cause:

Action:

IAM-3076069
Mandatory attribute {0} cannot be deleted.

Category:
Logging

Cause:

Action:

IAM-3076070
Request Data is invalid. Attribute {0} has null value. Attribute must have a non-null value.

Category:
Logging

Cause:

Action:

IAM-3076071
Error in username generation. No data was passed for user name generation.

Category:
Logging

Cause:

Action:

IAM-3076072
Error in username generation. Please provide {0} as expected by {1}.

Category:
Logging

Cause:

Action:

IAM-3076073
Error in username generation because all generated names already exist.

Category:
Logging

Cause:

Action:

IAM-3076074
Username generated from email ID {0} already exists.

Category:
Logging

Cause:

Action:

IAM-3076076
Error in username generation. Unable to fetch the policy {0}.

Category:
Logging

Cause:

Action:

IAM-3076077
Error retrieving User Entity Attributes for attribute length check in username generation.

Category:
Logging

Cause:

Action:

IAM-3076078
Error in user attribute reservation. Unable to fetch the plugin for LDAP reservation.

Category:
Logging

Cause:

Action:

IAM-3076079
Error in user attribute unreservation. Unable to fetch the plugin for LDAP reservation.

Category:
Logging

Cause:

Action:

IAM-3076080
Unable to fetch the value for system property {0}.

Category:
Logging

Cause:

Action:

IAM-3076081
Error in username generation. Please provide either {0} or {1} and {2} for {3}.

Category:
Logging

Cause:

Action:

IAM-3076082
Error in username generation. Length of {0} exceeds the expected length {1}.

Category:
Logging

Cause:

Action:

IAM-3076083
Another role with name {0} already exists in the same namespace {1}.

Category:
Logging

Cause:

Action:

IAM-3076084
Cannot find Role/s with key/s {0}.

Category:
Logging

Cause:

Action:

IAM-3076085
Cannot grant the role {0} to disabled/deleted user(s) {1}.

Category:
Logging

Cause:

Action:

IAM-3076086
An error occurred while withdrawing request.

Category:
Logging

Cause:

Action:

IAM-3076087
User cannot withdraw specified request.

Category:
Logging

Cause:

Action:

IAM-3076088
Value of attribute {0} is not of the required type {1}.

Category:
Logging

Cause:

Action:

IAM-3076089
An MLS value might have been passed for non-mls attribute.

Category:
Logging

Cause:

Action:

IAM-3076090
Cannot delete attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3076091
The name {0} is not unique in this organization. Choose another value for attribute commonName.

Category:
Logging

Cause:

Action:

IAM-3076092
The base value for displayName attribute cannot be deleted. Please specify a value for it.

Category:
Logging

Cause:

Action:

IAM-3076093
The base value for {0} should not be empty for modify operation.

Category:
Logging

Cause:

Action:

IAM-3076094
{0} should not be null for modify operation.

Category:
Logging

Cause:

Action:

IAM-3076095
The attribute {0} is a system controlled attribute and can not be passed in the PSO.

Category:
Logging

Cause:

Action:

IAM-3076096
The user {0} doesn''t have permission to access the request service.

Category:
Logging

Cause:

Action:

IAM-3076097
Common Name with value {0} already reserved.

Category:
Logging

Cause:

Action:

IAM-3076098
Error occurred while generating the Common Name

Category:
Logging

Cause:

Action:

IAM-3076099
The {0} with value {1} already exists under the container {2}

Category:
Logging

Cause:

Action:

IAM-3076100
The {0} with value {1} already exists or is reserved.

Category:
Logging

Cause:

Action:

IAM-3076101
Either the RDN {0} of the user is being modified, or the user container is changed without referential integrity being enabled on target LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3076102
The {0} entity does not exist.

Category:
Logging

Cause:

Action:

IAM-3076103
An error occurred while getting the container rules for LDAP.

Category:
Logging

Cause:

Action:

IAM-3076104
An error occurred while generating the Common Name. Invalid values passed for attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3076105
An error occurred while generating the Common Name. No data passed for Common Name generation.

Category:
Logging

Cause:

Action:

IAM-3076106
An error occurred while generating the Common Name. The Policy {0} for Common Name generation does not exist.

Category:
Logging

Cause:

Action:

IAM-3076107
An error occurred while generating the Common Name. Cannot fetch the policy {0}.

Category:
Logging

Cause:

Action:

IAM-3076108
An error occurred in Common Name generation. Please provide either {0} or {1} and {2} for {3}.

Category:
Logging

Cause:

Action:

IAM-3076109
An error occurred while retrieving the User Entity Attributes for attribute length check in Common Name generation.

Category:
Logging

Cause:

Action:

IAM-3076110
An error occurred while generating the Common Name. Length of {0} exceeds the expected length {1}.

Category:
Logging

Cause:

Action:

IAM-3076111
An error occurred while generating the Common Name. Length of one or more attributes exceeds the expected length.

Category:
Logging

Cause:

Action:

IAM-3076112
An error occurred while checking if a user already exists with the Common Name generated. {0}

Category:
Logging

Cause:

Action:

IAM-3076113
An error occurred while checking if the Common Name generated is already reserved. {0}

Category:
Logging

Cause:

Action:

IAM-3076114
An error occurred while generating the Common Name. Please provide {0} as expected by {1}.

Category:
Logging

Cause:

Action:

IAM-3076115
An error occurred while generating the Common Name because all of the generated names already exist.

Category:
Logging

Cause:

Action:

IAM-3076116
Common Name generated in pre process handler - {0}.

Category:
Logging

Cause:

Action:

IAM-3076117
Unable to generate a Common Name with the given data. Please specify a Common Name manually or provide the required data as per generation policy.

Category:
Logging

Cause:

Action:

IAM-3076118
The container {0} already contains a user with the Common Name {1}

Category:
Logging

Cause:

Action:

IAM-3076120
An error occurred while verifying if common name is unique.

Category:
Logging

Cause:

Action:

IAM-3076121
An error occurred while getting a connection to LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3076122
An error occurred while reserving user attributes {0} with values {1} in LDAP. Corresponding request ID is {2}.

Category:
Logging

Cause:

Action:

IAM-3076123
An error occurred while getting the LDAP container rules.

Category:
Logging

Cause:

Action:

IAM-3076124
The user with key {0} will be deleted by scheduler once the automatically delete on date {1} is reached.

Category:
Logging

Cause:

Action:

IAM-3076125
The RDN {0} of the role is being modified, or the role container has changed, without referential integrity being enabled on target LDAP directory.

Category:
Logging

Cause:

Action:

IAM-3076126
The user container is being changed to {0}, for which referential integrity needs to be enabled.

Category:
Logging

Cause:

Action:

IAM-3076127
The value {0} for sendNotificationTo parameter is not valid. Please enter valid value for sendNotificationTo parameter.

Category:
Logging

Cause:

Action:

IAM-3076128
Type mismatch for the attribute {0}. The type passed is {1}, but the corresponding type in the data set is {2}.

Category:
Logging

Cause:

Action:

IAM-3077001
Attribute name {0}

Category:
Logging

Cause:

Action:

IAM-3077002
Attribute value {0}

Category:
Logging

Cause:

Action:

IAM-3078001
The password change operation failed.

Category:
Logging

Cause:

Action:

IAM-3078002
Mail attribute of user or alternate email ids in sendNotificationTo list must be set for Reset password.

Category:
Logging

Cause:

Action:

IAM-3078003
Mail attribute of user (or manager) or alternate email ids in sendNotificationTo list must be set for Reset password.

Category:
Logging

Cause:

Action:

IAM-3079001
{0} is not supported value for batch request attribute {1}.

Category:
Logging

Cause:

Action:

IAM-3079002
Invalid batch request. Either batch request does not have children requests or children requests are not valid

Category:
Logging

Cause:

Action:

IAM-3079003
Invalid pso ID in lookup request. PSO ID must be provided as [identity/role]:[key/name/dn/guid]:[lookupvalue].

Category:
Logging

Cause:

Action:

IAM-3079004
An error occurred in lookup due to multiple match found.

Category:
Logging

Cause:

Action:

IAM-3079005
An error occurred while parsing the lookup DN passed in the request {0}.

Category:
Logging

Cause:

Action:

IAM-3079006
An error occurred while performing lookup operation. {0}

Category:
Logging

Cause:

Action:

IAM-3079007
User with given {0} {1} could not be found.

Category:
Logging

Cause:

Action:

IAM-3079008
Role with given {0} {1} could not be found.

Category:
Logging

Cause:

Action:

IAM-3079009
Requestor is not authorized to view the entity with given PSO identifier {0}.

Category:
Logging

Cause:

Action:

IAM-3080000
Request contains incorrect data.

Category:
Logging

Cause:

Action:

IAM-3080001
An error occured while getting list of multi-language enabled attributes from OIM - {0}

Category:
Logging

Cause:

Action:

IAM-3080003
An error has occurred while searching for a user.

Category:
Logging

Cause:

Action:

IAM-3080004
Multi Tenancy env is enabled

Category:
Logging

Cause:

Action:

IAM-3080005
Multi Tenancy env is not enabled

Category:
Logging

Cause:

Action:

IAM-3080006
Value provided for attribute {0} is not in {1} data type format

Category:
Logging

Cause:

Action:

IAM-3080007
Incorrect date format. Please enter date in format {0}. Unable to parse attribute {1} of date type {2}

Category:
Logging

Cause:

Action:

IAM-3080008
An error occurred while getting attribute {0} details - {1}

Category:
Logging

Cause:

Action:

IAM-3090000
Unable to map SCIM attribute {0} contained in request parameter {1}.

Category:
Logging

Cause:

Action:

IAM-3090001
Error while processing {0} operation with request {1} - {2}.

Category:
Logging

Cause:

Action:

IAM-3090002
Could not convert SCIM {0} to OIM {1}.

Category:
Logging

Cause:

Action:

IAM-3090003
Sorting not allowed on SCIM multivalued attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3090004
An attribute mapper is already registered for key {0}.

Category:
Logging

Cause:

Action:

IAM-3090006
Attribute {0} is not mapped.

Category:
Logging

Cause:

Action:

IAM-3090007
Unable to retrieve schema descriptor for URN {0}.

Category:
Logging

Cause:

Action:

IAM-3090008
{0} filter visitor only supports 2 sub-filters.

Category:
Logging

Cause:

Action:

IAM-3090009
Creation of organization returned null.

Category:
Logging

Cause:

Action:

IAM-3090010
Unsupported resource type {0}.

Category:
Logging

Cause:

Action:

IAM-3090011
Unable to retrieve attribute descriptor for name {0} in schema descriptor {1}.

Category:
Logging

Cause:

Action:

IAM-3090012
Only String with one character can be converted to Character type.

Category:
Logging

Cause:

Action:

IAM-3090013
Only multi-valued attributes can own a type {0} with type {1}.

Category:
Logging

Cause:

Action:

IAM-3090015
Values can not be assigned directly to complex attributes.

Category:
Logging

Cause:

Action:

IAM-3090016
Organization named {0} matched multiple organizations {1}.

Category:
Logging

Cause:

Action:

IAM-3090017
Unexpected exception while retrieving {0}.

Category:
Logging

Cause:

Action:

IAM-3090018
Unable to retrieve resource type and id from reference {0}.

Category:
Logging

Cause:

Action:

IAM-3090019
Unable to send response.

Category:
Logging

Cause:

Action:

IAM-3090020
Unable to find a method in {0} to {1} attribute {2}.

Category:
Logging

Cause:

Action:

IAM-3090021
Value {0} differs from the value referenced in {1}.

Category:
Logging

Cause:

Action:

IAM-3090022
SCIM attribute {0} is not searchable.

Category:
Logging

Cause:

Action:

IAM-3090023
Unexpected exception while retrieving members of group with id {0}.

Category:
Logging

Cause:

Action:

IAM-3090024
Unable to initialize static block in class {0}.

Category:
Logging

Cause:

Action:

IAM-3090025
Resource {0} with id {1} not found.

Category:
Logging

Cause:

Action:

IAM-3090026
SCIM mapped attribute name can not be null.

Category:
Logging

Cause:

Action:

IAM-3090027
Resource descriptor can not be null.

Category:
Logging

Cause:

Action:

IAM-3090028
Organization {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3090029
Unable to map SCIM attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3090031
Unsupported type {0} for mapping rule.

Category:
Logging

Cause:

Action:

IAM-3090032
Failed to read Oim configuration.

Category:
Logging

Cause:

Action:

IAM-3090039
Unsupported type for conversion {0}

Category:
Logging

Cause:

Action:

IAM-3090040
Unable to convert value {0} into {1}.

Category:
Logging

Cause:

Action:

IAM-3090041
The String to parse is empty.

Category:
Logging

Cause:

Action:

IAM-3090042
Incorrect character {0} while parsing "{1}" at index {2}.

Category:
Logging

Cause:

Action:

IAM-3090043
Invalid format: missing] while parsing "{0}".

Category:
Logging

Cause:

Action:

IAM-3090044
Search criteria {0} returned more than one result.

Category:
Logging

Cause:

Action:

IAM-3090045
SCIM attribute {0} is read-only and can not be patched.

Category:
Logging

Cause:

Action:

IAM-3090047
Either SCIM attribute name {0} or {1} is required.

Category:
Logging

Cause:

Action:

IAM-3090048
Error while retrieving passwordPolicyDescription.

Category:
Logging

Cause:

Action:

IAM-3090049
Unable to retrieve the id of the authenticated user: no entry.

Category:
Logging

Cause:

Action:

IAM-3090050
Unable to retrieve the value of the Oim attribute {0} from the Oim entity.

Category:
Logging

Cause:

Action:

IAM-3090051
Unable to assign the value {0} to the Oim attribute {1} of the Oim entity.

Category:
Logging

Cause:

Action:

IAM-3090052
Unable to clear the value of the Oim attribute {0} from the Oim entity.

Category:
Logging

Cause:

Action:

IAM-3090054
Challenge question can not be null.

Category:
Logging

Cause:

Action:

IAM-3090055
Challenge response can not be null.

Category:
Logging

Cause:

Action:

IAM-3090058
SCIM attribute name {0} is reserved for special calls and can not be used for standard PATCH.

Category:
Logging

Cause:

Action:

IAM-3090060
Expected attribute {0}.

Category:
Logging

Cause:

Action:

IAM-3090061
Unable to map OIM attribute {0} contained in SearchCriteria {1} to SCIM attribute.

Category:
Logging

Cause:

Action:

IAM-3090063
SearchCriteria type {0} does not exist in SCIM: {1}.

Category:
Logging

Cause:

Action:

IAM-3090066
The canonical name to parse has no schema URN: {0}.

Category:
Logging

Cause:

Action:

IAM-3091067
Unexpected end of String when parsing {0}.

Category:
Logging

Cause:

Action:

IAM-3091068
Unsupported query parameter for root search {0}.

Category:
Logging

Cause:

Action:

IAM-3091069
Unknown attribute {0} in resource {1}.

Category:
Logging

Cause:

Action:

IAM-3091070
Unsupported prefixed attribute name for root search {0}.

Category:
Logging

Cause:

Action:

IAM-3091071
Attribute name(s) {0} are not allowed at creation time.

Category:
Logging

Cause:

Action:

IAM-3091072
Unexpected resource type {0} for reference {1}.

Category:
Logging

Cause:

Action:

IAM-3091074
Unsupported operator for filter {0}.

Category:
Logging

Cause:

Action:

IAM-3091075
Invalid password format.

Category:
Logging

Cause:

Action:

IAM-3091076
The user with the key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3091077
No request found with the request ID {0}.

Category:
Logging

Cause:

Action:

IAM-3091078
The password policy with the key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-3091079
Unexpected sub-attribute {0} for attribute {1}.

Category:
Logging

Cause:

Action:

IAM-3091081
Unexpected value: {0}.

Category:
Logging

Cause:

Action:

IAM-3091082
Patch filter path applies to multi-valued attributes only.

Category:
Logging

Cause:

Action:

IAM-3091083
Only one value is allowed in a Patch operation with a path filter.

Category:
Logging

Cause:

Action:

IAM-3091084
The multi-valued attribute may be missing its type information.

Category:
Logging

Cause:

Action:

IAM-3091085
Setting userMembershipRule in POST or PUT request is not allowed. It can only be set using a PATCH request.

Category:
Logging

Cause:

Action:

IAM-3091086
Invalid username format {0}.

Category:
Logging

Cause:

Action:

IAM-3091088
Could not retrieve resource with the provided $ref {0}

Category:
Logging

Cause:

Action:

IAM-3091089
{0} is an invalid value for $ref attribute. Check the syntax

Category:
Logging

Cause:

Action:

IAM-3091090
Verification of $ref value {0} failed, reason : {1}.

Category:
Logging

Cause:

Action:

IAM-3091091
Specify either SCIM attribute {0} or {1} but not both.

Category:
Logging

Cause:

Action:

IAM-3091092
Unrecognized filter.

Category:
Logging

Cause:

Action:

IAM-3091093
Incorrect PATCH operation for attribute {0} : {1}.

Category:
Logging

Cause:

Action:

IAM-3091094
Cannot patch attribute members or userMembershipRule with other attributes.

Category:
Logging

Cause:

Action:

IAM-3091095
Cannot patch attribute active or locked with other attributes.

Category:
Logging

Cause:

Action:

IAM-3091096
Cannot patch attribute userMembershipRule with other attributes.

Category:
Logging

Cause:

Action:

IAM-3091097
Unexpected exception while retrieving catalog of group with id {0}.

Category:
Logging

Cause:

Action:

IAM-4020001
Cannot initialize the Auto Roles Engine - {0}.

Category:
Logging

Cause:

Action:

IAM-4020100
An error occurred while determining role changes - {0}.

Category:
Logging

Cause:

Action:

IAM-4020103
New user state is not available in orchestration.

Category:
Logging

Cause:

Action:

IAM-4020150
Rule key found in the context ({0}) is invalid. Setting change reason key to 0.

Category:
Logging

Cause:

Action:

IAM-4020151
Autoroles Engine has not been initialized properly.

Category:
Logging

Cause:

Action:

IAM-4020201
Cannot get the Entity Manager Service - {0}.

Category:
Logging

Cause:

Action:

IAM-4020202
Cannot retrieve the entity metadata for entity type {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4020203
Rule {0} is invalid and it is being ignored.

Category:
Logging

Cause:

Action:

IAM-4020204
An error occurred while parsing the rule expression and the rule {0} is being ignored- {1}.

Category:
Logging

Cause:

Action:

IAM-4020205
Rule {0} is invalid because it contains an element with an invalid attribute.

Category:
Logging

Cause:

Action:

IAM-4020206
Rule {0} is invalid because it does not contain any rule elements.

Category:
Logging

Cause:

Action:

IAM-4020207
The organization name {0} specified in the rule element is invalid.

Category:
Logging

Cause:

Action:

IAM-4020208
The organization name {0} specified in the rule element matches more than one organization.

Category:
Logging

Cause:

Action:

IAM-4020209
An error occurred while getting the organization information with the organization name {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4020210
The manager login {0} specified in the rule element is invalid.

Category:
Logging

Cause:

Action:

IAM-4020211
The manager login {0} specified in the rule element matches more than one user.

Category:
Logging

Cause:

Action:

IAM-4020212
An error occurred while getting the user information with the user login {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4020213
An error occurred while getting the active role determination rules - {0}.

Category:
Logging

Cause:

Action:

IAM-4020214
An error occurred while getting the rule definition with the rule key: {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4020215
Rule {0} failed to evaluate - {1}.

Category:
Logging

Cause:

Action:

IAM-4020216
An error occurred while getting roles associated with the rule with the rule key: {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4020217
An error occurred while getting the list of roles that were assigned manually - {0}.

Category:
Logging

Cause:

Action:

IAM-4020218
An error occurred while getting the list of roles that were assigned automatically by the Auto Roles Engine - {0}.

Category:
Logging

Cause:

Action:

IAM-4030000
The following exception occurred: {0}

Category:
Logging

Cause:

Action:

IAM-4030001
Access policy key found in the context ({0}) is invalid. Setting access policy key to 0.

Category:
Logging

Cause:

Action:

IAM-4030002
Unable to determine if account with key {0} is a service account.

Category:
Logging

Cause:

Action:

IAM-4030050
Failed to initialize Access Policy Engine.

Category:
Logging

Cause:

Action:

IAM-4030051
Access Policy Engine has not been initialized properly.

Category:
Logging

Cause:

Action:

IAM-4030052
An error occurred while determining account profile changes for user (key: {0}).

Category:
Logging

Cause:

Action:

IAM-4030053
Cannot determine if approval is necessary for provisioning resource (key: {0}).

Category:
Logging

Cause:

Action:

IAM-4030057
Cannot proceed with access policy harvesting since system property {0} is set to false.

Category:
Logging

Cause:

Action:

IAM-4030058
An error occured while encrypting policy key.

Category:
Logging

Cause:

Action:

IAM-4030200
An error occurred while evaluating policies for user (key: {0}).

Category:
Logging

Cause:

Action:

IAM-4030201
Cannot evaluate access policy for user (key: {0}). User does not exist.

Category:
Logging

Cause:

Action:

IAM-4030202
Cannot evaluate access policy for user (key: {0}). User is not active.

Category:
Logging

Cause:

Action:

IAM-4030203
Cannot mark members of role (key: {0}) for policy evaluation. Role does not exist.

Category:
Logging

Cause:

Action:

IAM-4030204
Cannot mark members of organization (key: {0}) for policy evaluation. Organization does not exist.

Category:
Logging

Cause:

Action:

IAM-4030205
Cannot mark members of policy (key: {0}) for policy evaluation. Policy does not exist.

Category:
Logging

Cause:

Action:

IAM-4030206
Cannot evaluate access policy for user (key: {0}). User is deleted. Marking policy evaluation as complete.

Category:
Logging

Cause:

Action:

IAM-4030207
Cannot proceed with access policy harvesting to link Access Policy (name: {0}) to user (key: {1})for account (key: {2}) due to following reason:

Category:
Logging

Cause:

Action:

IAM-4030208
The account (key:{0}) for user (key: {1}) is already linked to policy (key: {2}).

Category:
Logging

Cause:

Action:

IAM-4030209
The system property {0} is set to {1}. Set the value to true to support access policy harvesting.

Category:
Logging

Cause:

Action:

IAM-4030251
An error occurred while retrieving policy evaluation profile for user (key: {0}).

Category:
Logging

Cause:

Action:

IAM-4030252
An error occurred while writing policy evaluation profile for user (key: {0}).

Category:
Logging

Cause:

Action:

IAM-4030253
User (key: {0}) does not have a policy evaluation profile.

Category:
Logging

Cause:

Action:

IAM-4030255
An error occurred while completing access policy evaluation for user (key: {0}).

Category:
Logging

Cause:

Action:

IAM-4030256
An error occurred while marking members of role (key: {0}) for policy evaluation.

Category:
Logging

Cause:

Action:

IAM-4030257
An error occurred while marking members of organization (key: {0}) for policy evaluation.

Category:
Logging

Cause:

Action:

IAM-4030258
An error occurred while marking members of policy (key: {0}) for policy evaluation.

Category:
Logging

Cause:

Action:

IAM-4030302
Cannot create an access policy based request to provision resources {0} for user (key: {1}).

Category:
Logging

Cause:

Action:

IAM-4030303
An error occurred while retrieving {0} from {1} where {2} = {3}. Setting {0} to null.

Category:
Logging

Cause:

Action:

IAM-4030307
New user state is not available in orchestration.

Category:
Logging

Cause:

Action:

IAM-4030308
An error occurred in {0} while provisioning resource {1} to user {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4030309
An error occurred in {0} while disabling account with account key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4030310
An error occurred in {0} while revoking account with account key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4030311
An error occurred in {0} while enabling account with account key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4030401
An error occurred while retrieving details of user account (key: {0})

Category:
Logging

Cause:

Action:

IAM-4030502
Account discriminator field cannot be of type: {0}

Category:
Logging

Cause:

Action:

IAM-4040000
Entered method {0}/{1}

Category:
Logging

Cause:

Action:

IAM-4040001
Left method {0}/{1}

Category:
Logging

Cause:

Action:

IAM-4040002
Error getting Request Service : {0}

Category:
Logging

Cause:

Action:

IAM-4040004
Getting Beneficiary Information for beneficiary with Key : {0}

Category:
Logging

Cause:

Action:

IAM-4040005
SOD Check Property is Enabled

Category:
Logging

Cause:

Action:

IAM-4040006
SOD Check System Property {0} not found

Category:
Logging

Cause:

Action:

IAM-4040007
Submitting JMS to SOD Queue for Request with ID : {0}

Category:
Logging

Cause:

Action:

IAM-4040008
Submitted JMS to SOD Queue

Category:
Logging

Cause:

Action:

IAM-4040009
Connector IT Resource Name for request with ID {0} : {1}

Category:
Logging

Cause:

Action:

IAM-4040010
Connector IT Resource Key for request with ID {0} : {1}

Category:
Logging

Cause:

Action:

IAM-4040011
Created Transformation Layer Map to be passed to SIL

Category:
Logging

Cause:

Action:

IAM-4040012
Topology Name : {0}

Category:
Logging

Cause:

Action:

IAM-4040013
IDM System ID : {0} SOD Engine ID : {1} Target System ID : {2}

Category:
Logging

Cause:

Action:

IAM-4040014
Calling SIL Transformation Layer

Category:
Logging

Cause:

Action:

IAM-4040015
Returned from SIL Transformation Layer

Category:
Logging

Cause:

Action:

IAM-4040016
Executing SOD Analysis

Category:
Logging

Cause:

Action:

IAM-4040017
Completed SOD Analysis

Category:
Logging

Cause:

Action:

IAM-4040018
Error from SOD Invocation Library : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040019
SOD Tracking ID : {0}

Category:
Logging

Cause:

Action:

IAM-4040020
Updating Request DataSet with Tracking ID : {0}

Category:
Logging

Cause:

Action:

IAM-4040021
Updated Request DataSet

Category:
Logging

Cause:

Action:

IAM-4040022
Error Updating Request Data : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040023
Error Updating Request Stage and Status : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040024
No SOD Check for Request with ID : {0}

Category:
Logging

Cause:

Action:

IAM-4040025
No Connector IT Resource Found

Category:
Logging

Cause:

Action:

IAM-4040026
Searching for Request with 'SODCheckResultPending' Status

Category:
Logging

Cause:

Action:

IAM-4040027
Request with Key {0} has SOD Check Status {1}

Category:
Logging

Cause:

Action:

IAM-4040028
Error getting Pending SOD Requests {0} : {1}

Category:
Logging

Cause:

Action:

IAM-4040030
Error Getting Beneficiary Information : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040031
Error Getting Form Information : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040032
Error Getting IT Resource Information : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040033
Error Getting SOD Status Information : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040034
Entitlement Column not Defined : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040035
Error Getting Task Information : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040036
Error in Update of Task Information : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040037
Topology Not Found : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040038
Error in Query Execution : {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040039
Error Getting User Data Map: {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040043
Error Finding Open Provisioning Task Details: {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040044
Error Resubmitting Open Provisioning Tasks: {0} {1}

Category:
Logging

Cause:

Action:

IAM-4040045
Error Getting Process Instance Key for Request with ID: {0} : {1} {2}

Category:
Logging

Cause:

Action:

IAM-4040046
Error Getting Form Key for Process Instance with Key : {0} : {1} {2}

Category:
Logging

Cause:

Action:

IAM-4040047
SIL Topology Error : {0}

Category:
Logging

Cause:

Action:

IAM-4040048
Error from SOD Engine : {0}

Category:
Logging

Cause:

Action:

IAM-4051000
Failed to lookup the user with user key {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4051001
Error occurred while retrieving user entity data (key: {0}) - {1}

Category:
Logging

Cause:

Action:

IAM-4051002
Unable to read definition of user entity

Category:
Logging

Cause:

Action:

IAM-4052000
Cannot initialize the Password rule evaluator - {0}.

Category:
Logging

Cause:

Action:

IAM-4052001
Cannot get the Entity Manager Service - {0}.

Category:
Logging

Cause:

Action:

IAM-4052002
Cannot retrieve the entity metadata for entity type {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4052003
Rule {0} is invalid and it is being ignored.

Category:
Logging

Cause:

Action:

IAM-4052004
Error occurred while parsing the rule expression and the rule {0} is being ignored- {1}.

Category:
Logging

Cause:

Action:

IAM-4052005
Rule {0} is invalid, because it contains an element with invalid attribute.

Category:
Logging

Cause:

Action:

IAM-4052006
Rule {0} is invalid, because it does not contain any rule element.

Category:
Logging

Cause:

Action:

IAM-4052007
The organization name {0} specified in the rule element is invalid.

Category:
Logging

Cause:

Action:

IAM-4052008
The organization name {0} specified in the rule element matches more than one organization.

Category:
Logging

Cause:

Action:

IAM-4052009
Error occurred while getting the organization information with the organization name {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4052010
The manager login {0} specified in the rule element is invalid.

Category:
Logging

Cause:

Action:

IAM-4052011
The manager login {0} specified in the rule element matches more than one user.

Category:
Logging

Cause:

Action:

IAM-4052012
Error occurred while getting the user information with the user login {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4052013
Error occurred while getting the password policy rules - {0}.

Category:
Logging

Cause:

Action:

IAM-4052014
Error occurred while getting the rule definition with rule key: {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4052015
Rule {0} failed to evaluate - {1}.

Category:
Logging

Cause:

Action:

IAM-4052016
Error occurred while retrieving user entity data (key: {0}) - {1}

Category:
Logging

Cause:

Action:

IAM-4052017
Unable to read definition of user entity

Category:
Logging

Cause:

Action:

IAM-4053100
Error occurred while evaluating the password policies - {0}.

Category:
Logging

Cause:

Action:

IAM-4053101
Error occurred while updating the user password related fields - {0}.

Category:
Logging

Cause:

Action:

IAM-4054200
Error occurred while finding the user {0} provisioned resources - {1}.

Category:
Logging

Cause:

Action:

IAM-4054201
Error occurred while revoking the user {0} resources because deprovisioned date reached - {1}.

Category:
Logging

Cause:

Action:

IAM-4055300
Failed to initialize user audit handler.

Category:
Logging

Cause:

Action:

IAM-4055301
Key found in the context ({0}) is invalid. Setting change reason key to 0

Category:
Logging

Cause:

Action:

IAM-4055302
Error occurred while preparing to audit data for user (key: {0}). Unable to set the current user state - {1}.

Category:
Logging

Cause:

Action:

IAM-4055303
Error occurred while preparing the audit data for user (key: {0}). Unable to set current user state - {1}.

Category:
Logging

Cause:

Action:

IAM-4056000
Error occurred while provisioning Xellerate User resource to user"s {0} organization - {1}.

Category:
Logging

Cause:

Action:

IAM-4056001
Error occurred while completing Add User task in Xellerate User resource for user {0} and error is - {1}.

Category:
Logging

Cause:

Action:

IAM-4056002
Error occurred while reading system property {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4056003
Error occurred while updating creation date for user (key: {0} - {1}.

Category:
Logging

Cause:

Action:

IAM-4057000
Error occurred while retrieving menu items for the user {0}.

Category:
Logging

Cause:

Action:

IAM-4058000
Old user state is not available in orchestration

Category:
Logging

Cause:

Action:

IAM-4058001
New user state is not available in orchestration

Category:
Logging

Cause:

Action:

IAM-4058002
Old user states are not available in bulk orchestration

Category:
Logging

Cause:

Action:

IAM-4058003
New user states are not available in bulk orchestration

Category:
Logging

Cause:

Action:

IAM-4058004
Error occurred while propagating user management operations to corresponding accounts for user {0} - {1}

Category:
Logging

Cause:

Action:

IAM-4058005
Error occurred while propagating user changes to corresponding accounts for user {0} - {1}

Category:
Logging

Cause:

Action:

IAM-4058006
Error occurred while determining effect of user deletion on accounts for user {0} - {1}

Category:
Logging

Cause:

Action:

IAM-4058007
Old user state is not available in bulk orchestration

Category:
Logging

Cause:

Action:

IAM-4058008
New user state is not available in bulk orchestration

Category:
Logging

Cause:

Action:

IAM-4059000
IT Resource is not found for lookup criteria {0}

Category:
Logging

Cause:

Action:

IAM-4059001
Exception during lookup IT Resource

Category:
Logging

Cause:

Action:

IAM-4060000
An error occurred in {0} while fetching user with key {1} from orchestration parameters and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4060001
An error occurred in {0} while fetching application instance with key {1} from orchestration parameters and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4060004
An error occurred in {0} while provisioning application instance with key {1} to user with key {2} and the cause of the error is {3}

Category:
Logging

Cause:

Action:

IAM-4060005
An error occurred in {0} while fetching entitlement key {1} from orchestration parameters and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4060006
An error occurred in {0} while finding entitlement with entitlement Key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4060007
An error occurred in {0} while finding application instance with ITResource Key {1} and Object Key {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4060009
An error occurred in {0} while finding account details for user with key {1} in application instance with Key {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4060010
An error occurred in AccountTypeAndAppInstanceHandler: {0}

Category:
Logging

Cause:

Action:

IAM-4060020
Entitlement {0} is already granted to user {1}

Category:
Logging

Cause:

Action:

IAM-4060021
An error occurred while validating whether entitlement with key {0} is already provisioned to user with key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4060023
Entitlement {0} cannot be granted while the account is in {1} state.

Category:
Logging

Cause:

Action:

IAM-4060024
An error occurred in {0} while validating user {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4060025
An error occurred in {0} as user {1} is either in disabled or deleted status.

Category:
Logging

Cause:

Action:

IAM-4060026
An error occurred in {0} while changing account type to {1} for an account with id {2} as account has not been provisioned

Category:
Logging

Cause:

Action:

IAM-4060027
Unable to proceed with provisioning as the provisioning date is in future or de-provisioned date is in the past for user {0}.

Category:
Logging

Cause:

Action:

IAM-4060029
An error occurred while validating account {0} for granting entitlement {1}.

Category:
Logging

Cause:

Action:

IAM-4060030
An error occurred while validating account {0}. Application Instance key {1} of account does not match application instance key {2} of entitlement requested.

Category:
Logging

Cause:

Action:

IAM-4060031
An error occurred while validating account {0}. User key {1} of account does not match beneficiary key {2} of entitlement requested.

Category:
Logging

Cause:

Action:

IAM-4060032
Entitlement {0} cannot be granted as account to grant entitlement in is not identified.

Category:
Logging

Cause:

Action:

IAM-4060033
Unable to proceed with provisioning as the account start date or end date is not valid for user {0}

Category:
Logging

Cause:

Action:

IAM-4060034
An error occurred in {0} while resuming dependent requests of request {1} and the cause of the error is {2}.

Category:
Logging

Cause:

Action:

IAM-4060035
An error occurred in {0} while fetching account key from orchestration and the cause of the error is {1}.

Category:
Logging

Cause:

Action:

IAM-4060036
An error occurred in {0} while searching for application instance request and the cause of the error is {1}.

Category:
Logging

Cause:

Action:

IAM-4060037
An error occurred in {0} as primary account not found in application instance with key {1} provisioned to user {2}.

Category:
Logging

Cause:

Action:

IAM-4060040
An error occurred in {0} while identifying account for entitlement request {1} and the cause of the error is {2}.

Category:
Logging

Cause:

Action:

IAM-4060041
An error occurred in {0} while creating application instance request and the cause of the error is {1}.

Category:
Logging

Cause:

Action:

IAM-4060042
Request Id is null.

Category:
Logging

Cause:

Action:

IAM-4060043
An error occurred in {0} while getting request details for request {1} and the cause of the error is {2}.

Category:
Logging

Cause:

Action:

IAM-4060044
Entitlement {0} is not granted to user id {1}, hence cannot be modified.

Category:
Logging

Cause:

Action:

IAM-4060045
The entitlement {0} intended for this operation is in contradiction with the entitlement {1} provided as form data.

Category:
Logging

Cause:

Action:

IAM-4060046
An error occurred in {0} while entitlement {1} provisioned to user id {2} is being validated for modification.

Category:
Logging

Cause:

Action:

IAM-4060047
The bulk operation is not supported.

Category:
Logging

Cause:

Action:

IAM-4060048
An error occurred in {0} while identifying account for account request {1} and the cause of the error is {2}.

Category:
Logging

Cause:

Action:

IAM-4060049
An error occurred in {0} for orchProcess {1} and event {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4062060
No entitlement found with key {0}

Category:
Logging

Cause:

Action:

IAM-4062061
Entitlement with key {0} cannot be granted to account with key {1} while account is not in "Provisioned", "Enabled", or "Disabled" state.

Category:
Logging

Cause:

Action:

IAM-4062062
Entitlement with name {0} has already been requested via Request ID {1} and is in "Failed" status.

Category:
Logging

Cause:

Action:

IAM-4062063
Entitlement with name {0} already exists for Resource with key {1} and ITResource with key {2}.

Category:
Logging

Cause:

Action:

IAM-4062064
An error occurred while adding entitlements

Category:
Logging

Cause:

Action:

IAM-4062065
An error occurred while updating entitlements

Category:
Logging

Cause:

Action:

IAM-4062066
An error occurred while deleting entitlements

Category:
Logging

Cause:

Action:

IAM-4062067
An error occurred while granting entitlements

Category:
Logging

Cause:

Action:

IAM-4062068
An error occurred while updating entitlement instances

Category:
Logging

Cause:

Action:

IAM-4062069
An error occurred while revoking entitlement instances

Category:
Logging

Cause:

Action:

IAM-4062070
The attribute {0} is mandatory

Category:
Logging

Cause:

Action:

IAM-4062071
The form field with key {0} is not found

Category:
Logging

Cause:

Action:

IAM-4062072
The lookup value with key {0} is not found

Category:
Logging

Cause:

Action:

IAM-4062073
The resource object with key {0} is not found

Category:
Logging

Cause:

Action:

IAM-4062074
The form with key {0} is not found

Category:
Logging

Cause:

Action:

IAM-4062075
The IT Resource with key {0} is not found

Category:
Logging

Cause:

Action:

IAM-4062076
The entitlement with key {0} is not found

Category:
Logging

Cause:

Action:

IAM-4062077
An error occurred in {0} while granting entitlement as user having account {1} is not active.

Category:
Logging

Cause:

Action:

IAM-4062078
Exception occurred while invoking {0}

Category:
Logging

Cause:

Action:

IAM-4062079
Entitlement attribute configuration and matching key attribute for reconciliation field mapping are missing in {0}.

Category:
Logging

Cause:

Action:

IAM-4062080
Entitlement attribute not marked as key in reconciliation field mapping for {0}.

Category:
Logging

Cause:

Action:

IAM-4062081
Parent form details for process instance {0} cannot be found.

Category:
Logging

Cause:

Action:

IAM-4062082
Invalid Entitlement Instance for entitlement {0} for account with key {1}

Category:
Logging

Cause:

Action:

IAM-4062083
Entitlement with name {0} has already been requested, check the original request {1}.

Category:
Logging

Cause:

Action:

IAM-4062101
An error occurred in {0} when logged in user {1} performs action {2} for beneficiary user {3} for target entity {4} and the case of error is {5}.

Category:
Logging

Cause:

Action:

IAM-4062102
An error occurred in {0} as logged in user {1} does not have access to perform action {2} for beneficiary user {3} for target entity {4}.

Category:
Logging

Cause:

Action:

IAM-4062103
An error occurred in {0} when logged in user with key {1} performs action {2} for target entity with type {3} and entity key {4} and the cause of error is {5}.

Category:
Logging

Cause:

Action:

IAM-4062104
An error occurred in {0} as logged in user with key {1} does not have access to perform action {2} for target entity with type {3} and entity key {4}.

Category:
Logging

Cause:

Action:

IAM-4062105
An error occurred when trying to find application instance by key {0}.

Category:
Logging

Cause:

Action:

IAM-4062106
An error occurred in {0} when logged in user {1} performs {2} action and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4062107
An error occurred in {0} as logged in user {1} does not have access to perform action {2}.

Category:
Logging

Cause:

Action:

IAM-4062108
Password update is not supported in Modify Account operation. The change being made to the password field {0} for account id {1} is going to be ignored.

Category:
Logging

Cause:

Action:

IAM-4062109
The account id is required, but it is missing.

Category:
Logging

Cause:

Action:

IAM-4062110
Account End Date is after user end date for user {0}.

Category:
Logging

Cause:

Action:

IAM-4062111
Account Start Date is before user start date for user {0}.

Category:
Logging

Cause:

Action:

IAM-4062112
The logged-in user {0} is not a member of System Administrators group.

Category:
Logging

Cause:

Action:

IAM-4062113
Cannot proceed with operation {0} as Workflows have been disabled.

Category:
Logging

Cause:

Action:

IAM-4062114
Cannot proceed with operation select account for entitlement as Workflows have been disabled.

Category:
Logging

Cause:

Action:

IAM-4062115
Cannot proceed with operation provide information to create new account for entitlement as Workflows have been disabled.

Category:
Logging

Cause:

Action:

IAM-4062116
Considering the value of system property {0} to be true for operation {1} as there was an error reading it and the cause of the error is {2}.

Category:
Logging

Cause:

Action:

IAM-4062117
Considering the value of system property {0} to be true as there was an error reading it and the cause of the error is {1}.

Category:
Logging

Cause:

Action:

IAM-4062118
The input must contain at least one valid entitlement value

Category:
Logging

Cause:

Action:

IAM-4062119
An error occurred in {0} when logged in user {1} trying to get the entitlements for the given access policy keys.

Category:
Logging

Cause:

Action:

IAM-4062200
Invalid parent application instance key {0} .Please check that the resource level dependency is configured properly.

Category:
Logging

Cause:

Action:

IAM-4062201
Unsupported configuration.Multiple parent resource objects are defined for child resource with key {0}.

Category:
Logging

Cause:

Action:

IAM-4064000
An error occurred in {0} as application instance name is null.

Category:
Logging

Cause:

Action:

IAM-4064001
An error occurred in {0} as request type is null.

Category:
Logging

Cause:

Action:

IAM-4064002
An error occurred in {0} while getting application instance with name {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4064003
An error occurred in {0} while getting application instance with name {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4064004
An error occurred in {0} and the cause of error is {1}.

Category:
Logging

Cause:

Action:

IAM-4064005
An error occurred in {0} while creating request orchestration for provisioning application instance with key {1} to user with key {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4064006
An error occurred in {0} while creating request orchestration for provisioning entitlement with key {1} to user with key {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4064007
An error occurred in {0} while creating request orchestration for revoking entitlement instance with key {1} provisioned to user with key {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4064008
An error occurred in {0} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4064009
An error occurred in {0} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4064010
An error occurred in {0} as no form is associated to application instance {1}. This will cause problem while creating request. Please associate form to application instance {2}.

Category:
Logging

Cause:

Action:

IAM-4064011
An error occurred in {0} while creating request orchestration for modifying entitlement instance with key {1} provisioned to user with key {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4064012
Duplicate creation of an existing revoke entitlement instance with key {0} provisioned to user with key {1} is disallowed.

Category:
Logging

Cause:

Action:

IAM-4065002
An error occurred in {0} while finding account details with account-id {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4065004
An error occurred in {0} while disabling account with id {1} for user with key {2} the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4065008
An error occurred in {0} while finding application instance with key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4065009
An error occurred in {0} while enabling account with id {1} for the user with key {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4065010
An error occurred in {0} while provisioning application instance with key {1} to user with name {2} the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4065011
An error occurred in {0} while revoking account with id {1} for the user with key {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4065012
An error occurred in {0} while revoking entitlement {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4065013
An error occurred in {0} while updating entitlement {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4065014
An error occurred in {0} while changing the password for account with id {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4065015
An error occurred in {0} while getting details of account with key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4065016
An error occurred in {0} while getting accounts provisioned to user with key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4065017
An error occurred in {0} while getting accounts for which password can be reset for the user with key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4065018
An error occurred in {0} while getting accounts provisioned to user with key {1} in application instance with key {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4065019
An error occurred in {0} while changing account type to {1} for an account with id {2} as account is already {3}.

Category:
Logging

Cause:

Action:

IAM-4065020
An error occurred in {0} while changing account type for an account with id {1} as account type can not be changed from {2} account to {3} account.

Category:
Logging

Cause:

Action:

IAM-4065021
An error occurred in {0} while changing account type to {1} for an account with id {2} as account is a service account and can not be changed to {3} account.

Category:
Logging

Cause:

Action:

IAM-4065022
An error occurred in {0} while changing account type to {1} for an account with id {2} as account already has same status as {3}.

Category:
Logging

Cause:

Action:

IAM-4065023
An error occurred in {0} while changing account type to {1} for an account with id {2} for user with key {3} and the cause of error is {4}.

Category:
Logging

Cause:

Action:

IAM-4065024
An error occurred in {0} while modifying account with account id {1} for user {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4065025
An error occurred while trying to modify account.

Category:
Logging

Cause:

Action:

IAM-4065026
An error occurred while trying to find application instance by key.

Category:
Logging

Cause:

Action:

IAM-4065027
Ignoring the addition of duplicate child data that was detected in form {0}.

Category:
Logging

Cause:

Action:

IAM-4065028
Ignoring the deletion of child data which does not exist in form {0}.

Category:
Logging

Cause:

Action:

IAM-4065029
Ignoring the deletion of entitlement {0} as it does not exist.

Category:
Logging

Cause:

Action:

IAM-4065030
An error occurred in {0} while reading file {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4065031
An error occurred in {0} while updating disconnected provisioning URI for SOA tasks and the cause of error is {1}.

Category:
Logging

Cause:

Action:

IAM-4065032
An error occurred in {0} while verifying the password for account with id {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4065033
Password update is prohibited for account with id {0}. The account is not in "Provisioned", "Enabled", or "Disabled" state.

Category:
Logging

Cause:

Action:

IAM-4065034
An error occurred in {0} while processing upgraded request with key {1} having request details with app instance Key {2} and request beneficiary Key {3} which does not match with account details with app instance Key {4} and account beneficiary Key {5}

Category:
Logging

Cause:

Action:

IAM-4067000
An error occurred in {0} while finding account details as account with key {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-4067001
An error occurred in {0} while populating account data and the cause of error is {1}.

Category:
Logging

Cause:

Action:

IAM-4067002
An error occurred in {0} as account with key {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-4067003
An error occurred in {0} as form with key {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-4067004
An error occurred in {0} as form does not exist for process instance with key {1}.

Category:
Logging

Cause:

Action:

IAM-4067005
An error occurred in {0} as user with key {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-4067006
An error occurred in {0} as application instance with key {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-4067007
An error occurred while checking access for logged in user with key {0} to perform action {1} on entity with type {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-4067008
This operation requires approval. Access denied to logged in user with key {0} to perform direct operation {1} for entity type {2}.

Category:
Logging

Cause:

Action:

IAM-4067009
This operation requires approval. Access denied to logged in user with key {0} to perform direct operation {1} for target entity type {2} with key {3} for beneficiary entity type {4} with key {5}

Category:
Logging

Cause:

Action:

IAM-4067010
Access denied to logged in user with key {0} to perform direct operation {1} for entity type {2}.

Category:
Logging

Cause:

Action:

IAM-4067011
Access denied to logged in user with key {0} to perform direct operation {1} for target entity type {2} with key {3} for beneficiary entity type {4} with key {5}

Category:
Logging

Cause:

Action:

IAM-4067012
This operation requires approval. Access denied to logged in user with key {0} to perform direct operation {1} for entity type {2} with entity id {3}.

Category:
Logging

Cause:

Action:

IAM-4067013
Access denied to logged in user with key {0} to perform direct operation {1} for target entity type {2} with key {3}.

Category:
Logging

Cause:

Action:

IAM-4067014
An error occurred in {0} while checking access for logged in user with key {1} to perform action {2} on entity with type {3} and entity id {4} and the cause of error is {5}.

Category:
Logging

Cause:

Action:

IAM-4067015
An error occurred in {0} when logged in user with key {1} is publishing entities of type {2} for the keys {3} and the cause of error is {4}.

Category:
Logging

Cause:

Action:

IAM-4067016
An error occurred in {0} while updating account type of existing account from {1} to {2} for user with key {3} by executing query {4}.

Category:
Logging

Cause:

Action:

IAM-4067017
An error occurred in {0} while updating account type to {1} for account with key {2} and user with key {3} by executing query {4}

Category:
Logging

Cause:

Action:

IAM-4067018
An error occurred in {0} as application instance key is updated for account with id {1}. The existing application instance key is {2} and modified key is {3}.

Category:
Logging

Cause:

Action:

IAM-4067019
An error occurred in {0} as process form does not match for existing account and modified account with id {1}. The existing process form key is {2} and modified key is {3}.

Category:
Logging

Cause:

Action:

IAM-4067022
Access denied in {0} to user with key {1} to perform direct operation {2} for target entity type {3} and the cause of error is {4} .

Category:
Logging

Cause:

Action:

IAM-4067023
An error occurred in {0} when user with key {1} performs direct operation {2} for target entity type {3} and the cause of error is {4}.

Category:
Logging

Cause:

Action:

IAM-4067024
An error occurred in {0} while checking access for logged in user with key {1} to perform action {2} on entity with type {3} and entity id {4} and approval obligation name {5}.

Category:
Logging

Cause:

Action:

IAM-4067025
An error occurred in {0} as access denied to logged in user with key {1} to perform action {2} for entity {3} .

Category:
Logging

Cause:

Action:

IAM-4067026
An error occurred in {0} as entitlement instance with key {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-4067027
An error occurred in {0} and the cause of error is {1}.

Category:
Logging

Cause:

Action:

IAM-4067028
An error occurred in {0} as user with key {1} is in status {2}.

Category:
Logging

Cause:

Action:

IAM-4067029
An error occurred in {0} as account with id {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-4067030
An error occurred in {0} as entity-publication cache refresh failed for {1} with key {2}.

Category:
Logging

Cause:

Action:

IAM-4067031
An error occurred in {0} as access denied to logged in user with key {1} to search for {2} with key {3}.

Category:
Logging

Cause:

Action:

IAM-4067032
An error occurred in {0} as entity key is not passed for {1} and hence access denied to logged in user with key {2} to search for {3} with key {4}.

Category:
Logging

Cause:

Action:

IAM-4067033
An error occurred in {0} while finding details for request key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4067034
An error occurred in {0} as process instance with key {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-4067040
An error occurred in {0} as there is no entitlement instance associated with account key {1} and entitlement key {2}.

Category:
Logging

Cause:

Action:

IAM-4067041
Configuration Error: The entitlement field cannot be determined as there is no field marked as Entitlement in form {0}.

Category:
Logging

Cause:

Action:

IAM-4067042
Configuration Error: The entitlement field cannot be determined as there are multiple fields marked as Entitlement but no field marked as OIAParentAttribute in form {0}.

Category:
Logging

Cause:

Action:

IAM-4067043
Configuration Error: The entitlement field cannot be determined as there are multiple fields marked as OIAParentAttribute and Entitlement in form {0}.

Category:
Logging

Cause:

Action:

IAM-4067044
An error occurred in {0} as account start and end dates are not valid.

Category:
Logging

Cause:

Action:

IAM-4067045
Entitlement start/end date is not valid for entitlement with name {1} for account {2}.

Category:
Logging

Cause:

Action:

IAM-4067046
An error occurred in {0} as ApplicationObjectclass with name {1} already exists.

Category:
Logging

Cause:

Action:

IAM-4067047
ApplicationObjectclass with ID {0} is not found.

Category:
Logging

Cause:

Action:

IAM-4067048
ApplicationObjectclass with name {0} is not found.

Category:
Logging

Cause:

Action:

IAM-4067049
An error occurred in {0} while creating ApplicationObjectclass {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4067050
An error occurred in {0} while creating schema for ApplicationObjectclass {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-4067051
Access denied to logged in user with key {0} to perform direct operation {1} for entity type {2}.

Category:
Logging

Cause:

Action:

IAM-4067052
An error occurred in {0} for ApplicaionObjectclass with name {1} and the cause of error is {2} .

Category:
Logging

Cause:

Action:

IAM-4067053
An error occurred in {0} while deleting ApplicaionObjectclass with ID {1} and the cause of error is {2} .

Category:
Logging

Cause:

Action:

IAM-4067054
An error occurred in {0} while finding ApplicaionObject and the cause of error is {2} .

Category:
Logging

Cause:

Action:

IAM-4067055
An error occurred while retrieving count of revoke entitlement request existing for a particular entitlement .

Category:
Logging

Cause:

Action:

IAM-4068000
An error occurred while executing the schedule job - {0}, and the corresponding error message is - {1}

Category:
Logging

Cause:

Action:

IAM-4068001
An error occurred while updating account with application instance and type.

Category:
Logging

Cause:

Action:

IAM-4068002
An error occurred while trying to get account key for user from database.

Category:
Logging

Cause:

Action:

IAM-4068003
An error occurred while waiting for user thread to die.

Category:
Logging

Cause:

Action:

IAM-4068004
An error occurred while trying to get user key from database.

Category:
Logging

Cause:

Action:

IAM-4068005
An error occurred while executing method - {0}, in the schedule job - {1}, and the corresponding error message is - {2}

Category:
Logging

Cause:

Action:

IAM-4068006
An error occurred while populating version information for application instance {0} in method {1}, and the error message is - {2}

Category:
Logging

Cause:

Action:

IAM-4068007
An error occurred while retrieving process instances for application instance {0} in method {1}, and the error message is - {2}

Category:
Logging

Cause:

Action:

IAM-4068008
An error occurred while setting or updating the process form data for form {0} and process instance key {1} , and the error message is - {2}

Category:
Logging

Cause:

Action:

IAM-4068009
Waiting to complete form upgrade for application instance {0} in method {1}

Category:
Logging

Cause:

Action:

IAM-4068010
An error occurred in {0} while trying to enabling account with account key - {1}

Category:
Logging

Cause:

Action:

IAM-4068011
Schedule job {0} is only applicable to run in DB mode.

Category:
Logging

Cause:

Action:

IAM-4069000
Error invoking SOA Composite for account with orc_key {0}

Category:
Logging

Cause:

Action:

IAM-4069001
Error getting payload details for account with orc_key {0}

Category:
Logging

Cause:

Action:

IAM-4069002
Payload is null for account with orc_key {0}

Category:
Logging

Cause:

Action:

IAM-4069020
Application Instance Name passed is null or empty.

Category:
Logging

Cause:

Action:

IAM-4069021
An error occurred while executing query {0} with parameter {1}.

Category:
Logging

Cause:

Action:

IAM-4069022
An error occurred while handling result data set for query {0} with parameter {1}.

Category:
Logging

Cause:

Action:

IAM-4069023
Error occurred while finding replacement string for entity with max length {0} and query {1}.

Category:
Logging

Cause:

Action:

IAM-4069024
Error occurred while replacing {0} with {1} in xml file.

Category:
Logging

Cause:

Action:

IAM-4069025
Error occurred while importing {0} file through Deployment Manager.

Category:
Logging

Cause:

Action:

IAM-4069026
Error occurred while creating ITResource with name {0} of type {1}.

Category:
Logging

Cause:

Action:

IAM-4069027
No records returned for query {0} with entity name {1}.

Category:
Logging

Cause:

Action:

IAM-4069028
Application Instance name {0} already exists.Please use different name for Application Instance.

Category:
Logging

Cause:

Action:

IAM-4069029
Replacement Sting is null.

Category:
Logging

Cause:

Action:

IAM-4070000
ITResource Instance with key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-4070001
Resource with key {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-4070002
Application Instance already created for Resource {0} and ITResource {1}.

Category:
Logging

Cause:

Action:

IAM-4070003
Application Instance name {0} already exists. Please use different name for Application Instance.

Category:
Logging

Cause:

Action:

IAM-4070007
An error occurred while executing prepared statement {0}.

Category:
Logging

Cause:

Action:

IAM-4070008
An error occurred while handling result data set {0}.

Category:
Logging

Cause:

Action:

IAM-5010000
Generic Information: {0}

Category:
Logging

Cause:

Action:

IAM-5010001
Calling stored procedure - {0}

Category:
Logging

Cause:

Action:

IAM-5010002
{0} reconciliation for {1} with ID {2}

Category:
Logging

Cause:

Action:

IAM-5010003
Failed in {0} for {1} with ID {2}

Category:
Logging

Cause:

Action:

IAM-5010004
Unknown entity type {0} with ID {1}

Category:
Logging

Cause:

Action:

IAM-5010006
The following exception occurred: {0}

Category:
Logging

Cause:

Action:

IAM-5010007
{0} with ID {1} does not exist

Category:
Logging

Cause:

Action:

IAM-5010010
Incorrect {0} match with ID {1}

Category:
Logging

Cause:

Action:

IAM-5010012
NULL value attribute will not be processed - {0}

Category:
Logging

Cause:

Action:

IAM-5010014
Processing data - {0}

Category:
Logging

Cause:

Action:

IAM-5010015
No data for event {0}

Category:
Logging

Cause:

Action:

IAM-5010016
Data Received:

Category:
Logging

Cause:

Action:

IAM-5010017
Created due to reconciliation event {0}

Category:
Logging

Cause:

Action:

IAM-5010018
Updated due to reconciliation event {0}

Category:
Logging

Cause:

Action:

IAM-5010019
Deleted due to reconciliation event {0}

Category:
Logging

Cause:

Action:

IAM-5010020
The reconciliation event {0} is already linked

Category:
Logging

Cause:

Action:

IAM-5010021
The reconciliation event {0} has been closed

Category:
Logging

Cause:

Action:

IAM-5010022
Cannot perform action {0} - Event {1} has no matches found

Category:
Logging

Cause:

Action:

IAM-5010026
Failed to execute stored procedure - {0}

Category:
Logging

Cause:

Action:

IAM-5010027
Failed to provision {0} with ID {1} for event {2}

Category:
Logging

Cause:

Action:

IAM-5010028
Failed to revoke account {0} for event {1}

Category:
Logging

Cause:

Action:

IAM-5010029
Failed to set status to {0} for account {1}

Category:
Logging

Cause:

Action:

IAM-5010030
Failed to insert notification task for event {0}

Category:
Logging

Cause:

Action:

IAM-5010031
Failed to set response for notification task with event ID {0}

Category:
Logging

Cause:

Action:

IAM-5010034
Invalid child status {0} with ID {1}

Category:
Logging

Cause:

Action:

IAM-5010035
Create record in child table - {0}

Category:
Logging

Cause:

Action:

IAM-5010036
Created child records {0} in table {1}

Category:
Logging

Cause:

Action:

IAM-5010038
Failed to create child record in table {0} for target entry {1}

Category:
Logging

Cause:

Action:

IAM-5010039
Modify record in child table {0}

Category:
Logging

Cause:

Action:

IAM-5010040
Modified child records {0} in table {1}

Category:
Logging

Cause:

Action:

IAM-5010041
mapped to Column {0}

Category:
Logging

Cause:

Action:

IAM-5010042
Inserting record in child table {0}

Category:
Logging

Cause:

Action:

IAM-5010043
Updating record in child table {0} with primary key {1}

Category:
Logging

Cause:

Action:

IAM-5010044
Deleting record in child table {0} with primary key {1}

Category:
Logging

Cause:

Action:

IAM-5010045
Matched child records - {0}

Category:
Logging

Cause:

Action:

IAM-5010046
Executing {0} task with ID {1}

Category:
Logging

Cause:

Action:

IAM-5010048
No child data for event {0}

Category:
Logging

Cause:

Action:

IAM-5010050
Cannot execute job {0} with status {1}

Category:
Logging

Cause:

Action:

IAM-5010052
Submit task for {0}

Category:
Logging

Cause:

Action:

IAM-5010055
Failed to modify child record in table {0} for entry {1}

Category:
Logging

Cause:

Action:

IAM-5010056
Failed to delete child record in table {0} for entry {1}

Category:
Logging

Cause:

Action:

IAM-5010059
Child matched table already contains entries for event {0}

Category:
Logging

Cause:

Action:

IAM-5010061
Failed to retrieve the ORC key using OIU key - {0}

Category:
Logging

Cause:

Action:

IAM-5010062
Failed to retrieve the ORC key using OIO key - {0}

Category:
Logging

Cause:

Action:

IAM-5010063
Failed to retrieve the UD entry in table {0} using ORC key - {1}

Category:
Logging

Cause:

Action:

IAM-5010064
Failed to retrieve the UD entry in child table {0} using key - {1}

Category:
Logging

Cause:

Action:

IAM-5010065
Failed to retrieve the ORC key for user - {0}

Category:
Logging

Cause:

Action:

IAM-5010066
No action is performed for event {0} with status {1}

Category:
Logging

Cause:

Action:

IAM-5010067
Target table {0} is empty

Category:
Logging

Cause:

Action:

IAM-5010069
Failed to obtain unit of work to add event assignment for event {0}

Category:
Logging

Cause:

Action:

IAM-5010071
Failed to obtain unit of work to update job status for job {0}

Category:
Logging

Cause:

Action:

IAM-5010073
No action performed since account match is not found

Category:
Logging

Cause:

Action:

IAM-5010078
The event with event ID {0} was not processed as it is a future dated event

Category:
Logging

Cause:

Action:

IAM-5011002
Event Linking Failure: failed to link Event {0} to User {1}.

Category:
Logging

Cause:

Action:

IAM-5011007
Event Closure failure for Event(s): {0}

Category:
Logging

Cause:

Action:

IAM-5011008
Event(s) {0} successfully Closed.

Category:
Logging

Cause:

Action:

IAM-5011009
OIM Entity successfully created from Event {0}.

Category:
Logging

Cause:

Action:

IAM-5011010
OIM Entity creation failure for Event {0}.

Category:
Logging

Cause:

Action:

IAM-5011012
Search parameter {0} invalid: {1}. "%" not allowed. The parameter will be ignored during the Search.

Category:
Logging

Cause:

Action:

IAM-5011013
Parameter {0} is too long. The parameter will be ignored during the Search.

Category:
Logging

Cause:

Action:

IAM-5011014
The Event {0} was successfully Linked to Account {1}.

Category:
Logging

Cause:

Action:

IAM-5011015
Linking Event {0} to Account {1} failed with Exception: {2}.

Category:
Logging

Cause:

Action:

IAM-5011016
Linking Event {0} to Account {1} failed with a conversion Error. The Event or selected Account IDs may be invalid.

Category:
Logging

Cause:

Action:

IAM-5011017
Linking Event {0} to User {1} failed with Exception: {2}.

Category:
Logging

Cause:

Action:

IAM-5011018
Linking Event {0} to User {1} failed with a conversion Error. The Event or selected Account IDs may be invalid.

Category:
Logging

Cause:

Action:

IAM-5011019
The Event {0} was successfully Linked to User {1}.

Category:
Logging

Cause:

Action:

IAM-5011020
Failed to reapply Reconciliation Rules on Event(s) {0}. Originating user: {1)

Category:
Logging

Cause:

Action:

IAM-5011021
Successfully reapplied Reconciliation Rules on Event(s) {0}. Originating user: {1)

Category:
Logging

Cause:

Action:

IAM-5011022
Failed to invoke the Reconciliation Management Service from {0}.

Category:
Logging

Cause:

Action:

IAM-5011023
Failed to invoke the Reconciliation Management CLIENT Service from {0}. LOGIN Error.

Category:
Logging

Cause:

Action:

IAM-5011025
Reconciliation Search: Starting to Fetch...

Category:
Logging

Cause:

Action:

IAM-5011026
Reconciliation Search: MIN Index = {0}, MAX Index = {1}, MAX SIZE = {2}.

Category:
Logging

Cause:

Action:

IAM-5011027
Reconciliation Search: Search Results size = {0}.

Category:
Logging

Cause:

Action:

IAM-5011028
Reconciliation Search: Search Complete.

Category:
Logging

Cause:

Action:

IAM-5011029
Reconciliation Search: Counted Size = {0}.

Category:
Logging

Cause:

Action:

IAM-5011030
Account matching Event {0} successfully deleted.

Category:
Logging

Cause:

Action:

IAM-5011031
Failed to deleted Account matching Event {0}.

Category:
Logging

Cause:

Action:

IAM-5011032
EVS Service initialized... Service : {0}

Category:
Logging

Cause:

Action:

IAM-5011033
User "{0}" is not authorized to perform Reconciliation Action: {1}.

Category:
Logging

Cause:

Action:

IAM-5011034
User "{0}" is granted access to Reconciliation Action: {1}.

Category:
Logging

Cause:

Action:

IAM-5011038
It Resource information is incorrect

Category:
Logging

Cause:

Action:

IAM-5011102
Event Details: ID

Category:
Logging

Cause:

Action:

IAM-5011107
Organization Name

Category:
Logging

Cause:

Action:

IAM-5012000
Skipping event with id {0} due to invalid profile name

Category:
Logging

Cause:

Action:

IAM-5012001
Default Metrics Sensor tree creation failure. Message: {0}, Exception: {1}

Category:
Logging

Cause:

Action:

IAM-5012003
Processing reconciliation event with id : {0}

Category:
Logging

Cause:

Action:

IAM-5012004
Invalid event id : {0}

Category:
Logging

Cause:

Action:

IAM-5012005
User id : {0}

Category:
Logging

Cause:

Action:

IAM-5012007
Setting field {0} to value {1}

Category:
Logging

Cause:

Action:

IAM-5012008
Error occurred while retrieving event data : {0}

Category:
Logging

Cause:

Action:

IAM-5012009
Error occurred during processing of user creation in the action engine : {0}

Category:
Logging

Cause:

Action:

IAM-5012011
Error occurred during processing of account creation in the action engine: {0}

Category:
Logging

Cause:

Action:

IAM-5012014
Error occurred while establishing link to account with orc_key {0} : {1}

Category:
Logging

Cause:

Action:

IAM-5012015
Creating event with ID {0} in the reconciliation events database table using Stored Procedures

Category:
Logging

Cause:

Action:

IAM-5012021
Updating reconciliation event with ID {0}

Category:
Logging

Cause:

Action:

IAM-5012022
Executing Toplink ReportQuery to get search count using expression {0}

Category:
Logging

Cause:

Action:

IAM-5012023
Number of events is {0}

Category:
Logging

Cause:

Action:

IAM-5012024
No attribute data found for event {0}

Category:
Logging

Cause:

Action:

IAM-5012025
Executing Toplink ReadAllQuery to get search results using expression {0}

Category:
Logging

Cause:

Action:

IAM-5012026
Executing stored procedure {0}

Category:
Logging

Cause:

Action:

IAM-5012028
Error encountered while executing procedure {0} : {1}

Category:
Logging

Cause:

Action:

IAM-5012029
Invalid SQL property name {0}

Category:
Logging

Cause:

Action:

IAM-5012030
Invalid object name {0}

Category:
Logging

Cause:

Action:

IAM-5012031
Logged in userkey {0}

Category:
Logging

Cause:

Action:

IAM-5012032
Invalid username {0}

Category:
Logging

Cause:

Action:

IAM-5012039
Unsupported operator {0}

Category:
Logging

Cause:

Action:

IAM-5012040
Invalid search criteria provided

Category:
Logging

Cause:

Action:

IAM-5012041
Invalid User UID {0}

Category:
Logging

Cause:

Action:

IAM-5012042
No events for retry

Category:
Logging

Cause:

Action:

IAM-5012045
The User with ID {0} was found

Category:
Logging

Cause:

Action:

IAM-5012046
No deferred events to run

Category:
Logging

Cause:

Action:

IAM-5012047
Could not retrieve multilingual enablement flag, due to exception: {0}

Category:
Logging

Cause:

Action:

IAM-5012126
Error during MDS initialization

Category:
Logging

Cause:

Action:

IAM-5012200
Profile for - {0} object does not exist

Category:
Logging

Cause:

Action:

IAM-5012201
Job Name or Job run id does not exists for {0}

Category:
Logging

Cause:

Action:

IAM-5012202
Invalid Profile - {0}

Category:
Logging

Cause:

Action:

IAM-5012206
Reconciliation event {0} completed successfully

Category:
Logging

Cause:

Action:

IAM-5012219
The Reconciliation key {0} does not exist in cache

Category:
Logging

Cause:

Action:

IAM-5012220
Child tables only supported at account-level

Category:
Logging

Cause:

Action:

IAM-5012223
The Event with key {0} has already been closed

Category:
Logging

Cause:

Action:

IAM-5012224
Get the object details of {0}

Category:
Logging

Cause:

Action:

IAM-5012226
An exception occurred: {0}

Category:
Logging

Cause:

Action:

IAM-5012227
Exception occurred while inserting data into table {0} due to {1}

Category:
Logging

Cause:

Action:

IAM-5012228
Invalid data - {0} against Date format {1} for key {2}

Category:
Logging

Cause:

Action:

IAM-5012233
Reconciliation event closing was unsuccessful

Category:
Logging

Cause:

Action:

IAM-5012234
Not a valid reconciliation key {0}

Category:
Logging

Cause:

Action:

IAM-5012235
Orc_key not found for the given object key {0}

Category:
Logging

Cause:

Action:

IAM-5012236
Organization reconciliation not supported

Category:
Logging

Cause:

Action:

IAM-5012237
Creating event with ID {0} with change type {1} in the reconciliation events database table using Stored Procedures

Category:
Logging

Cause:

Action:

IAM-5012238
Batch Id {0} returned using Stored Procedures

Category:
Logging

Cause:

Action:

IAM-5012239
Batch Completion Flag {0} returned using Stored Procedures

Category:
Logging

Cause:

Action:

IAM-5012250
Oim attribute name is {0} and value is {1}

Category:
Logging

Cause:

Action:

IAM-5012251
Inside the {0} method

Category:
Logging

Cause:

Action:

IAM-5012252
Exit from the {0} method

Category:
Logging

Cause:

Action:

IAM-5012253
Required attribute name {0} and value does not exist

Category:
Logging

Cause:

Action:

IAM-5012254
Unable to retrieve default date format

Category:
Logging

Cause:

Action:

IAM-5012255
ProfileID does not exists in the cache for the event ID {0}

Category:
Logging

Cause:

Action:

IAM-5012256
Event status is "Data Received"

Category:
Logging

Cause:

Action:

IAM-5012262
Entity type User not supported for child data matching

Category:
Logging

Cause:

Action:

IAM-5012282
Entity type is {0} for delete detected accounts

Category:
Logging

Cause:

Action:

IAM-5012288
The Reconciliation key is {0} and object key is {1}

Category:
Logging

Cause:

Action:

IAM-5012296
Operation {0} is not authorized

Category:
Logging

Cause:

Action:

IAM-5012297
Attribute {0} with value {1} of the reconciled object {2} has invalid format. You should correct it on the target/trusted resource and retry recon again.

Category:
Logging

Cause:

Action:

IAM-5012298
A required attribute {0} is missing from the reconciled object {1}. You should correct it on the target/trusted resource and retry recon again.

Category:
Logging

Cause:

Action:

IAM-5012301
Deleting data from UD table {0}

Category:
Logging

Cause:

Action:

IAM-5012302
Executing SQL query {0}

Category:
Logging

Cause:

Action:

IAM-5012304
Deleting data from table {0} with id as {1}

Category:
Logging

Cause:

Action:

IAM-7130001
General Search Information: {0}

Category:
Logging

Cause:

Action:

IAM-7130002
Getting details for catalog : {0}

Category:
Logging

Cause:

Action:

IAM-7130103
Searching catalog items with search criteria as {0}.

Category:
Logging

Cause:

Action:

IAM-7130104
Searching catalog items with search criteria TAG as {0} and Category as {1}.

Category:
Logging

Cause:

Action:

IAM-7130106
Executing query {0} to see if catalog is Open or Closed.

Category:
Logging

Cause:

Action:

IAM-7130107
Start time to execute the count query is {0}.

Category:
Logging

Cause:

Action:

IAM-7130108
End time to execute the count query is {0}.

Category:
Logging

Cause:

Action:

IAM-7130109
Start time to execute the Search query is {0}.

Category:
Logging

Cause:

Action:

IAM-7130110
End time to execute the Search query is {0}.

Category:
Logging

Cause:

Action:

IAM-7130111
Invalid Search criteria.Missing mandatory argument Argument.TAG.

Category:
Logging

Cause:

Action:

IAM-7130112
Sort field is invalid.

Category:
Logging

Cause:

Action:

IAM-7130113
Cannot pass Sort criteria with Sort filed as NULL.

Category:
Logging

Cause:

Action:

IAM-7130114
Start Time to Filter {0} result by calling API : {1}.

Category:
Logging

Cause:

Action:

IAM-7130115
End Time to Filter {0} result by calling API : {1}.

Category:
Logging

Cause:

Action:

IAM-7130118
Open catalog Query : {0}.

Category:
Logging

Cause:

Action:

IAM-7130119
Closed catalog Query : {0}.

Category:
Logging

Cause:

Action:

IAM-7130120
Problem occurred while catalog search, Please contact your Administrator.

Category:
Logging

Cause:

Action:

IAM-7130121
Cannot Find the Base entity values as EntityType or Key is missing.

Category:
Logging

Cause:

Action:

IAM-7130122
No result returned.

Category:
Logging

Cause:

Action:

IAM-7130123
The search is not available at this time due to text index maintenance. Check with your Administrator.

Category:
Logging

Cause:

Action:

IAM-7130124
Your search is resulted in too many terms. Narrow your search.

Category:
Logging

Cause:

Action:

IAM-7130125
Search token caused Oracle text DRG issue, DB exception is :{0}

Category:
Logging

Cause:

Action:

IAM-7130126
Finding Catalog, Criteria is :{0}

Category:
Logging

Cause:

Action:

IAM-7130127
Operator :{0} not supported for :{1} data type

Category:
Logging

Cause:

Action:

IAM-7130128
Issue with getting of system property with name{0} so setting the value to -1 as default.

Category:
Logging

Cause:

Action:

IAM-7130129
System property with name{0} is not having value as "true" or "false" so treating value as false as default valule.

Category:
Logging

Cause:

Action:

IAM-7130130
Invalid SearchCriteria for Finder API. Column Name {0} doesnot exists.

Category:
Logging

Cause:

Action:

IAM-7130131
Error while searching for role with key {0}. Error: {1}

Category:
Logging

Cause:

Action:

IAM-7130132
Issue with getting of system property with name{0} so setting it to default value.

Category:
Logging

Cause:

Action:

IAM-7130201
Catalog with ID {0} successfully created.

Category:
Logging

Cause:

Action:

IAM-7130202
Catalog with name {0} successfully Updated.

Category:
Logging

Cause:

Action:

IAM-7130211
No Detail found for specified catalog item .

Category:
Logging

Cause:

Action:

IAM-7130212
Unable to update Catalog with name : {0} Please search and try again.

Category:
Logging

Cause:

Action:

IAM-7130213
Failed to update the Catalog items with Entity name as {0}.

Category:
Logging

Cause:

Action:

IAM-7130214
Trying to update catalog Item with the values : {0}.

Category:
Logging

Cause:

Action:

IAM-7130215
Error while metadata seeding: {0}.

Category:
Logging

Cause:

Action:

IAM-7130216
No userdefined tags defined for the given catalog details.

Category:
Logging

Cause:

Action:

IAM-7130217
Cannot retrieve information for the details provided, provide EntityKey and Type to get details.

Category:
Logging

Cause:

Action:

IAM-7130218
Data provided for getting User defined tag is inCorrect.

Category:
Logging

Cause:

Action:

IAM-7130219
User defined tags for catalog item is {0}.

Category:
Logging

Cause:

Action:

IAM-7130221
Cannot get details of the information provided.

Category:
Logging

Cause:

Action:

IAM-7130222
You do not have permission to add the catalog item.

Category:
Logging

Cause:

Action:

IAM-7130223
You do not have permission to update the catalog item.

Category:
Logging

Cause:

Action:

IAM-7130224
You do not have permission to retrieve details of the catalog item.

Category:
Logging

Cause:

Action:

IAM-7130225
Category cannot be Null.

Category:
Logging

Cause:

Action:

IAM-7130304
No of rows updated : {0}

Category:
Logging

Cause:

Action:

IAM-7130307
Error while closing connection : {0}

Category:
Logging

Cause:

Action:

IAM-7130308
Incorrect value for Mode. Expected values are {0} or {1}.

Category:
Logging

Cause:

Action:

IAM-7130309
Date cannot be null. Enter a valid date.

Category:
Logging

Cause:

Action:

IAM-7130310
I/O Error occurred while parsing of metadata file, check that the file is not corrupt and try to rerun Catalog Synchronization Job.

Category:
Logging

Cause:

Action:

IAM-7130311
OIM_SP_HarvestCatalogData stored procedure error occurred during harvesting, check OIM DB state/logs for details.

Category:
Logging

Cause:

Action:

IAM-7130312
You cannot specify {0} header in catalog metadata file.

Category:
Logging

Cause:

Action:

IAM-7130313
File path is empty. Please provide file path, its must when mode is METADATA.

Category:
Logging

Cause:

Action:

IAM-7130314
Invalid file path, Check value in File path.

Category:
Logging

Cause:

Action:

IAM-7130315
This record {0} is not processed because Category is not provided for the record in CSV.

Category:
Logging

Cause:

Action:

IAM-7130316
{0} batch executed while enriching catalog.

Category:
Logging

Cause:

Action:

IAM-7130318
Start Time for Parsing of XML is {0}.

Category:
Logging

Cause:

Action:

IAM-7130319
End Time for Parsing of XML is {0}.

Category:
Logging

Cause:

Action:

IAM-7130320
Total Time for XML processing is {0}.

Category:
Logging

Cause:

Action:

IAM-7130321
Data provided for getting hierarchical details is not complete.

Category:
Logging

Cause:

Action:

IAM-7130322
Specified path for seeding technical glossary is not a valid Directory path.

Category:
Logging

Cause:

Action:

IAM-7130323
File path is empty. Please provide file path, its must when mode is Technical Glossary.

Category:
Logging

Cause:

Action:

IAM-7130401
Metadata successfully added to catalog.

Category:
Logging

Cause:

Action:

IAM-7130402
Metadata successfully updated for catalog.

Category:
Logging

Cause:

Action:

IAM-7130403
Metadata successfully deleted for catalog.

Category:
Logging

Cause:

Action:

IAM-7130404
An error occurred while updating metadata for catalog.

Category:
Logging

Cause:

Action:

IAM-7130405
An error occurred while deleting metadata for catalog.

Category:
Logging

Cause:

Action:

IAM-7130407
An error occurred while adding metadata definition to catalog.

Category:
Logging

Cause:

Action:

IAM-7130412
User with ID {0} don''t have permission to update the Metadata definition.

Category:
Logging

Cause:

Action:

IAM-7130413
User with ID {0} don''t have permission to create the Metadata definition.

Category:
Logging

Cause:

Action:

IAM-7130414
User with ID {0} don''t have permission to delete the Metadata definition.

Category:
Logging

Cause:

Action:

IAM-7130415
Metadata Update Query: {0}.

Category:
Logging

Cause:

Action:

IAM-7130416
Data provided for adding metadata is inCorrect.

Category:
Logging

Cause:

Action:

IAM-7130417
Problem Updating Metadata definition DB_COLUMN_NAME.

Category:
Logging

Cause:

Action:

IAM-7130418
OOTB field cannot be modified.

Category:
Logging

Cause:

Action:

IAM-7130422
Non-Searchable Metadata cannot be made Searchable.

Category:
Logging

Cause:

Action:

IAM-7130423
Updating {0} request data set and the opertion is {1}.

Category:
Logging

Cause:

Action:

IAM-7130424
After adding UDF in Catalog updating DataSets.

Category:
Logging

Cause:

Action:

IAM-7130425
After updating UDF in Catalog updating DataSets.

Category:
Logging

Cause:

Action:

IAM-7130426
After deleting UDF in Catalog updating DataSets.

Category:
Logging

Cause:

Action:

IAM-7130427
Attribute name passed is incorrect.

Category:
Logging

Cause:

Action:

IAM-7130428
Display name or UDF information passed is incorrect.

Category:
Logging

Cause:

Action:

IAM-7130507
"Role Cannot be synched in Catalog as catalog is null"

Category:
Logging

Cause:

Action:

IAM-7130601
Exception while closing Connection Or ResultSet Object {0}.

Category:
Logging

Cause:

Action:

IAM-7130602
Error while retrieving User details in Catalog, check OIM diagnostic log for details.

Category:
Logging

Cause:

Action:

IAM-7130603
Not able to retrieve information for the catalog entity with ID {0} ,entityType {1} and entityName {2}.

Category:
Logging

Cause:

Action:

IAM-7130604
This operation is not supported for Express Edition.

Category:
Logging

Cause:

Action:

IAM-7130605
Exception occurred while calculating auto tag.

Category:
Logging

Cause:

Action:

IAM-7130606
Inside finder method of Catalog, where clause of finder query is {0}.

Category:
Logging

Cause:

Action:

IAM-7130607
Complex searchCriteria is not supported for finding Categories in Catalog.

Category:
Logging

Cause:

Action:

IAM-7130608
Issue while building XPATH for the Hierarchical Data.

Category:
Logging

Cause:

Action:

IAM-7130651
Issue with getting of system property with name{0} so considering auditing as disabled.

Category:
Logging

Cause:

Action:

IAM-7130652
Problem in setting old catalog state in catalog data access object.

Category:
Logging

Cause:

Action:

IAM-7130653
Problem in setting old catalog state in catalog data access object with flush changes.

Category:
Logging

Cause:

Action:

IAM-7130654
Problem in setting new catalog state in catalog data access object.

Category:
Logging

Cause:

Action:

IAM-7130655
Error from audit engine while passing catalog information to audit engine.

Category:
Logging

Cause:

Action:

IAM-7130656
Key found in the context ({0}) is invalid. Setting change reason key to 0

Category:
Logging

Cause:

Action:

IAM-7130701
Not able to process entity with name {0} for attribute {1}, either the name is not correct or the attribute name is wrong.

Category:
Logging

Cause:

Action:

IAM-7130801
Not able to process entities, entity type is missing from catalog item.

Category:
Logging

Cause:

Action:

IAM-7130802
No entity to process.

Category:
Logging

Cause:

Action:

IAM-7130803
Problem during insert of catalog entities.

Category:
Logging

Cause:

Action:

IAM-7130804
Problem during update of catalog entities.

Category:
Logging

Cause:

Action:

IAM-7130805
Catalog entities successfully inserted.

Category:
Logging

Cause:

Action:

IAM-7130806
Catalog entities successfully updated.

Category:
Logging

Cause:

Action:

IAM-7130807
Problem during delete of catalog entities.

Category:
Logging

Cause:

Action:

IAM-7130808
Catalog entities successfully deleted.

Category:
Logging

Cause:

Action:

IAM-7860001
Import successful for object with name : {0} and type : {1}

Category:
Logging

Cause:

Action:

IAM-7860002
This code can only handle import for type : {0} therefore unable to handle import for object with name : {1} and type : {2}

Category:
Logging

Cause:

Action:

IAM-7860003
Import failed for object with name : {0} and type : {1}

Category:
Logging

Cause:

Action:

IAM-7860004
Error searching objects of type : {0}

Category:
Logging

Cause:

Action:

IAM-7860005
Empty list of {0} type objects to export

Category:
Logging

Cause:

Action:

IAM-7860006
Empty list of object types to export

Category:
Logging

Cause:

Action:

IAM-7860007
Empty list of objects to import

Category:
Logging

Cause:

Action:

IAM-7860008
Loading Class : {0}

Category:
Logging

Cause:

Action:

IAM-7860009
Loading class : {0} failed

Category:
Logging

Cause:

Action:

IAM-7860010
Error Trace :

Category:
Logging

Cause:

Action:

IAM-7860011
Unable to find the handler to be invoked for object of type : {0} and name : {1}

Category:
Logging

Cause:

Action:

IAM-7860101
File size too large, is {0} bytes

Category:
Logging

Cause:

Action:

IAM-8010000
{0} [{1}] Reassigned [{2}]

Category:
Logging

Cause:

Action:

IAM-8010001
Delegated [{0}]

Category:
Logging

Cause:

Action:

IAM-8010002
Roles [{0}]

Category:
Logging

Cause:

Action:

IAM-8010003
Application Instances [{0}]

Category:
Logging

Cause:

Action:

IAM-8010004
Entitlements [{0}]

Category:
Logging

Cause:

Action:

IAM-8010005
Error searching for catalog entry for entitlement key {0} : {1}.

Category:
Logging

Cause:

Action:

IAM-8010006
Verification

Category:
Logging

Cause:

Action:

IAM-8010007
Server exception #{0}.

Category:
Logging

Cause:

Action:

IAM-8010008
For more information, search the server''s error log for an entry containing this key: #{0}.

Category:
Logging

Cause:

Action:

IAM-8010009
User {0} cannot be delegated to self: self certification is not allowed.

Category:
Logging

Cause:

Action:

IAM-8010010
Task with uid {0} cannot be completed.

Category:
Logging

Cause:

Action:

IAM-8010011
Unable to complete this certification because the following tasks are not complete:{0}.

Category:
Logging

Cause:

Action:

IAM-8010013
Cannot create certification definition "{0}". A definition with the same name already exists.

Category:
Logging

Cause:

Action:

IAM-8010014
Certification definition to save is null.

Category:
Logging

Cause:

Action:

IAM-8010015
Cannot create certification because the open certification named {0} has duplicate type {1}, certifier {2}, and organization {3}.

Category:
Logging

Cause:

Action:

IAM-8010016
Error deserializing certification configuration.

Category:
Logging

Cause:

Action:

IAM-8010017
Certification configuration for certification ID {0} is null or cannot be deserialized.

Category:
Logging

Cause:

Action:

IAM-8010020
Some certification line items to be undelegated (restored) to certification task {0} (ID {1}) were not delegated or are already undelegated, and will be skipped.

Category:
Logging

Cause:

Action:

IAM-8010022
Error finding alternate reviewer for self-certification in certification {0}: Alternate reviewer not set in configuration.

Category:
Logging

Cause:

Action:

IAM-8010023
Error finding alternate reviewer for self-certification in certification {0}: Certifier {1} has no manager.

Category:
Logging

Cause:

Action:

IAM-8010024
Error finding alternate reviewer for self-certification in certification {0}: Specified alternate [user key {1}] does not exist.

Category:
Logging

Cause:

Action:

IAM-8010026
Error creating entitlement certification {0}: No attributes specified.

Category:
Logging

Cause:

Action:

IAM-8010029
Certification entity of type {0} and ID {1} not found for certification {2} (ID {3}).

Category:
Logging

Cause:

Action:

IAM-8010030
Certification entity of type {0} and ID {1} not found for certification {2} (ID {3}) and task UID {4}.

Category:
Logging

Cause:

Action:

IAM-8010031
Error creating phase two verification tasks for certification {0} (ID {2}): No tasks with delegated items found.

Category:
Logging

Cause:

Action:

IAM-8010032
Error calculating final review decision for certification {0} (ID {1}): No final review decision for user ID {2}.

Category:
Logging

Cause:

Action:

IAM-8010033
Error calculating final review decision for certification {0} (ID {1}): No final review decision for entitlement ID {2}.

Category:
Logging

Cause:

Action:

IAM-8010034
Error while saving certification configuration.

Category:
Logging

Cause:

Action:

IAM-8010035
Certification configuration is invalid. See server error log for details (Exception type {0}).

Category:
Logging

Cause:

Action:

IAM-8010036
[name not available]

Category:
Logging

Cause:

Action:

IAM-8010037
Certification job with name "{0}" already exists. Please try again with a different name for the certification job.

Category:
Logging

Cause:

Action:

IAM-8010038
Error loading certification.

Category:
Logging

Cause:

Action:

IAM-8010039
Error loading certification task.

Category:
Logging

Cause:

Action:

IAM-8010040
Delegation is not configured for certification {0} (ID {1}).

Category:
Logging

Cause:

Action:

IAM-8010041
Delegate reviewer not found (user ID {0}).

Category:
Logging

Cause:

Action:

IAM-8010042
Delegate reviewer may not delegate.

Category:
Logging

Cause:

Action:

IAM-8010043
Delegation not permitted during certification verification or final review.

Category:
Logging

Cause:

Action:

IAM-8010045
Certification {0} (ID {1}) has invalid type {2}.

Category:
Logging

Cause:

Action:

IAM-8010046
Certification not found for ID {0}.

Category:
Logging

Cause:

Action:

IAM-8010047
Certification {0} (ID {1}) is not active.

Category:
Logging

Cause:

Action:

IAM-8010048
Certification task not found for ID {0}.

Category:
Logging

Cause:

Action:

IAM-8010049
Certification task {0} (ID {1}) is not active.

Category:
Logging

Cause:

Action:

IAM-8010050
Reassignment is not configured for certification {0} (ID {1}).

Category:
Logging

Cause:

Action:

IAM-8010051
Reassign reviewer not found (user ID {0}).

Category:
Logging

Cause:

Action:

IAM-8010052
Delegate reviewer may not reassign.

Category:
Logging

Cause:

Action:

IAM-8010053
Reassignment not permitted during certification verification or final review.

Category:
Logging

Cause:

Action:

IAM-8010054
Method invocation allowed only during phase one review (current phase {0}).

Category:
Logging

Cause:

Action:

IAM-8010056
Cannot delegate to primary reviewer {0}.

Category:
Logging

Cause:

Action:

IAM-8010057
User {0} cannot be reassigned to self: self certification is not allowed.

Category:
Logging

Cause:

Action:

IAM-8010062
Please note: if user is revoked, user will never show up in Phase 2; because it implies the user no longer works in company so no point in reviewing the access. However, if user is certified but access is revoked then user will show up in Phase 2.

Category:
Logging

Cause:

Action:

IAM-8011000
Error parsing command line parameters : missing value for option {0}.

Category:
Logging

Cause:

Action:

IAM-8011001
IT Resource definition {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-8011002
IT Resource instance {0} already exists.

Category:
Logging

Cause:

Action:

IAM-8011003
Cannot create IT Resource instance {0} : {1}.

Category:
Logging

Cause:

Action:

IAM-8011004
UDF column {0} already exists.

Category:
Logging

Cause:

Action:

IAM-8011005
Cannot create UDF {0} : {1}.

Category:
Logging

Cause:

Action:

IAM-8011006
Cannot create job: scheduled task definition {0} does not exist.

Category:
Logging

Cause:

Action:

IAM-8011007
Cannot create scheduled job: {0}

Category:
Logging

Cause:

Action:

IAM-8011009
Cannot create system property {0} : {1}.

Category:
Logging

Cause:

Action:

IAM-8011010
Scheduled job {0} created successfully.

Category:
Logging

Cause:

Action:

IAM-8011011
OPAM-OIM integration setup script.

Category:
Logging

Cause:

Action:

IAM-8011012
system property {0} updated successfully.

Category:
Logging

Cause:

Action:

IAM-8011013
system property {0} created successfully.

Category:
Logging

Cause:

Action:

IAM-8011014
Could not initialize : {0}.

Category:
Logging

Cause:

Action:

IAM-8011015
Error parsing command line parameters : unknown option : {0}.

Category:
Logging

Cause:

Action:

IAM-8011016
Enter {0} :

Category:
Logging

Cause:

Action:

IAM-8011017
OPAM IT resource name

Category:
Logging

Cause:

Action:

IAM-8011018
OIM URL (t3://oimhost:oimport for weblogic or corbaloc:iiop:oimhost:oimport for websphere)

Category:
Logging

Cause:

Action:

IAM-8011019
OIM username

Category:
Logging

Cause:

Action:

IAM-8011020
OIM user password

Category:
Logging

Cause:

Action:

IAM-8011021
OPAM server name

Category:
Logging

Cause:

Action:

IAM-8011022
OPAM server port

Category:
Logging

Cause:

Action:

IAM-8011023
OPAM user

Category:
Logging

Cause:

Action:

IAM-8011024
OPAM user password

Category:
Logging

Cause:

Action:

IAM-8011025
ID Store IT resource name

Category:
Logging

Cause:

Action:

IAM-8011026
Context (weblogic.jndi.WLInitialContextFactory for weblogic or com.ibm.websphere.naming.WsnInitialContextFactory for websphere)

Category:
Logging

Cause:

Action:

IAM-8011027
UDF column created successfully

Category:
Logging

Cause:

Action:

IAM-8011028
IT Resource {0} created successfully.

Category:
Logging

Cause:

Action:

IAM-8019001
Caught exception during workflow services invocation.

Category:
Logging

Cause:

Action:

IAM-8019002
Error assigning certification {0} (ID {1}).

Category:
Logging

Cause:

Action:

IAM-8019003
Error signing-off workflow task taskUid {0} for assignee {1}.

Category:
Logging

Cause:

Action:

IAM-8019004
Error closing workflow task taskUid {0}.

Category:
Logging

Cause:

Action:

IAM-8019005
Error retrieving task title(s) for taskUid(s) {0}.

Category:
Logging

Cause:

Action:

IAM-8019006
For certification task UID {0}, expected one task assigned, but workflow services reports {1} tasks assigned.

Category:
Logging

Cause:

Action:

IAM-8019007
For certification task UID {0}, workflow services reports {1} task(s) assigned, but none assigned to user {2}.

Category:
Logging

Cause:

Action:

IAM-8019008
The specified user must match the logged-in user. Expected: {0} (ID {1}); actual: {2} (ID {3}).

Category:
Logging

Cause:

Action:

IAM-8019009
Error checking user {0} (ID {1}) access to workflow task UID {2}.

Category:
Logging

Cause:

Action:

IAM-8019011
Unable to find group for task UID {0} while checking task assignee.

Category:
Logging

Cause:

Action:

IAM-8019012
Unable to verify role grants for task UID {0} while checking task assignee.

Category:
Logging

Cause:

Action:

IAM-8020001
Caught exception for access policy result set.

Category:
Logging

Cause:

Action:

IAM-8020002
Caught exception while trying to find access policy with id {0} in getPolicyById method. See exception trace in next log record.

Category:
Logging

Cause:

Action:

IAM-8020003
No policies found for role {0}.

Category:
Logging

Cause:

Action:

IAM-8020004
Caught exception while loading policies for role {0} in loadPoliciesByRole method. See exception trace in next log record.

Category:
Logging

Cause:

Action:

IAM-8020005
Bypassing certification of policy {0} because the policy is missing an IT resource name.

Category:
Logging

Cause:

Action:

IAM-8020006
Access policy with id of {0} not found.

Category:
Logging

Cause:

Action:

IAM-8020007
Resource types associated for the policy with key {0} in OIM {1}.

Category:
Logging

Cause:

Action:

IAM-8020008
EndPoint identifier field for namespace name {0} is {1}.

Category:
Logging

Cause:

Action:

IAM-8020009
Caught exception in getOIMNamespaceFormFieldKeyNameMap method processing key list {0}. See exception trace in next log record.

Category:
Logging

Cause:

Action:

IAM-8020010
Caught exception in getOIMNamespaceProcessFormKeys method.

Category:
Logging

Cause:

Action:

IAM-8020011
Entitlement attribute record {0}.

Category:
Logging

Cause:

Action:

IAM-8020012
Unable to find child form data information for policyKey {0}, resourcetype id {1}, endpoint field {2} and attribute form key {3}.

Category:
Logging

Cause:

Action:

IAM-8020013
Unable to find access policy resource data for policyKey {0}, resourcetype id {1}, endpoint field {2} and attribute form key {3}.

Category:
Logging

Cause:

Action:

IAM-8020014
Unable to find resource type information for policyKey {0}, resourcetype id {1} and endpoint field {2}.

Category:
Logging

Cause:

Action:

IAM-8020015
Caught exception in getEndPointPolicyAttributeMap method while getting attribute values for policyKey {0}, resourcetype id {1}, endpoint field {2} and attribute form key {3}. See exception trace in next log record.

Category:
Logging

Cause:

Action:

IAM-8020016
EndPoint Name is {0}.

Category:
Logging

Cause:

Action:

IAM-8020017
Caught exception in getEndPointPolicyAttributeMap method while parsing endpointkey string.

Category:
Logging

Cause:

Action:

IAM-8020018
Missing catalog entry for policy attribute value {0}.

Category:
Logging

Cause:

Action:

IAM-8020019
Policy endPoint attribute details map contains {0}.

Category:
Logging

Cause:

Action:

IAM-8020020
No catalog entries for policy id {0} and resource type id {1}.

Category:
Logging

Cause:

Action:

IAM-8020021
No attribute definitions for policy id {0} and resource type id {1}.

Category:
Logging

Cause:

Action:

IAM-8020022
Exception stack trace for previous log record.

Category:
Logging

Cause:

Action:

IAM-8020023
EndPoint {0} found for the given endpoint key {1} in OIM.

Category:
Logging

Cause:

Action:

IAM-8020024
Caught exception in createPolicy method while trying to find application instances.

Category:
Logging

Cause:

Action:

IAM-8020025
Caught exception while getting endpointName {0} and oimEndpointKey {1} in getEndpointName method. See exception trace in next log record.

Category:
Logging

Cause:

Action:

IAM-8020026
Could not find value for accountName property for Sdk: {0}. Make sure AccountName property is properly configured in process form. Skipping account with this sdk.

Category:
Logging

Cause:

Action:

IAM-8020027
Exception encountered while loading policy violations for user {0}

Category:
Logging

Cause:

Action:

IAM-8020028
Exception encountered while loading policy violation causes for user {0}, policy violation: {1}

Category:
Logging

Cause:

Action:

IAM-8020029
Could not find value for AccountName(Login) property for Application Instance {0}. Make sure AccountName(Login) property is set for all users in Application Instance {0}.

Category:
Logging

Cause:

Action:

IAM-8030001
Certification job creation aborted: Unknown certification type of {0}.

Category:
Logging

Cause:

Action:

IAM-8030002
Certification job creation aborted: Certification definition "{0}" was not found.

Category:
Logging

Cause:

Action:

IAM-8030003
Certification job creation aborted: No certification definition specified for the certification creation task.

Category:
Logging

Cause:

Action:

IAM-8030004
Certification job creation aborted: No arguments specified for certification creation task.

Category:
Logging

Cause:

Action:

IAM-8030005
Certification job creation aborted: Invalid criteria type {0} for user certification.

Category:
Logging

Cause:

Action:

IAM-8030006
User certification creation failed with the following error: {0}.

Category:
Logging

Cause:

Action:

IAM-8030007
Unable to create a user certification {0} task for certifier {1}.

Category:
Logging

Cause:

Action:

IAM-8030008
User certification creation succeeded but with the following errors:

Category:
Logging

Cause:

Action:

IAM-8030009
Certification not created for organization "{0}": Organization has no manager assigned to it.

Category:
Logging

Cause:

Action:

IAM-8030010
Certification not created for organization "{0}": Manager "{1}" was not found.

Category:
Logging

Cause:

Action:

IAM-8030011
Certification not created for organization "{0}": Organization has no users to certify.

Category:
Logging

Cause:

Action:

IAM-8030012
Certification not created for organization "{0}": All users were filtered out by event listener.

Category:
Logging

Cause:

Action:

IAM-8030013
Certification will not contain user "{0}": User has no manager.

Category:
Logging

Cause:

Action:

IAM-8030014
Certification will not contain user "{0}": User was not found in the system.

Category:
Logging

Cause:

Action:

IAM-8030015
Role certification will not contain role "{0}": Role has no role owner assigned to it.

Category:
Logging

Cause:

Action:

IAM-8030018
Unable to create entitlement certification {0}: Data owner ID {1} is invalid.

Category:
Logging

Cause:

Action:

IAM-8030019
Entitlement certification not created for entitlement {0}: Entitlement has no certifier.

Category:
Logging

Cause:

Action:

IAM-8030020
All user IDs for the selected organizations were filtered out by event listener.

Category:
Logging

Cause:

Action:

IAM-8030024
User certification {0} not created: No users to certify.

Category:
Logging

Cause:

Action:

IAM-8030026
Caught exception retrieving accounts for attribute value during processing entitlement certification {0}. See exception trace in next log record.

Category:
Logging

Cause:

Action:

IAM-8030028
Caught exception while persisting entitlement certification.

Category:
Logging

Cause:

Action:

IAM-8030030
Entitlement certification creation failed with the following errors: {0}.

Category:
Logging

Cause:

Action:

IAM-8030031
Entitlement certification creation succeeded but with the following errors:

Category:
Logging

Cause:

Action:

IAM-8030032
Application instance certification creation failed with the following error: {0}.

Category:
Logging

Cause:

Action:

IAM-8030033
Application instance certification creation succeeded but with the following errors:

Category:
Logging

Cause:

Action:

IAM-8030034
Role certification creation failed with the following error: {0}.

Category:
Logging

Cause:

Action:

IAM-8030035
Role certification creation succeeded but with the following errors:

Category:
Logging

Cause:

Action:

IAM-8030036
Entitlement certification creation failed. No catalog results for tag: {0}.

Category:
Logging

Cause:

Action:

IAM-8030037
Entitlement certification creation failed. No entitlement definition owners specified.

Category:
Logging

Cause:

Action:

IAM-8030038
Entitlement certification creation failed. No entitlement definitions specified.

Category:
Logging

Cause:

Action:

IAM-8030039
Entitlement certification creation failed. No entitlements were found.

Category:
Logging

Cause:

Action:

IAM-8030040
Certification job creation aborted: Workflows are disabled.

Category:
Logging

Cause:

Action:

IAM-8030108
Certification not created for Application Instance Owner {0} : Application Instance owner Id is not valid.

Category:
Logging

Cause:

Action:

IAM-8030109
Unable to create a certification {0} for certifier {1}.

Category:
Logging

Cause:

Action:

IAM-8030110
Unable to create a certification task for certification {0} and certifier {1}.

Category:
Logging

Cause:

Action:

IAM-8030111
Application Instance {0} has no owner, will not be included in certification.

Category:
Logging

Cause:

Action:

IAM-8030113
Certification {0} not created for selected roles: Role selection does not have any roles with high item risk to certify.

Category:
Logging

Cause:

Action:

IAM-8030114
Certification not created for organization {0}: Organization has no roles with high item risk to certify.

Category:
Logging

Cause:

Action:

IAM-8030116
Certifier: {0} has some roles that are included in certification {1} Need to create alternative certification.

Category:
Logging

Cause:

Action:

IAM-8030119
Certification {0} not created. Certification has no content to be certified.

Category:
Logging

Cause:

Action:

IAM-8030120
Certification {0} not created. Certification has no incremental content to be certified.

Category:
Logging

Cause:

Action:

IAM-8030121
User {0} has no accounts to certify and will not be included in certification

Category:
Logging

Cause:

Action:

IAM-8030122
No entitlements found for owner {0}. Certification will not be created.

Category:
Logging

Cause:

Action:

IAM-8030126
User "{0}" is not valid, will not be included in certification.

Category:
Logging

Cause:

Action:

IAM-8030127
Role "{0}" is not valid, will not be included in certification.

Category:
Logging

Cause:

Action:

IAM-8030130
Certification {0} not created. Base selection criteria did not return any results.

Category:
Logging

Cause:

Action:

IAM-8030131
Unable to communicate with SOA Server. Please check if SOA server is up and running.

Category:
Logging

Cause:

Action:

IAM-8030132
Certification creation job stopping before any processing. Certification Definition: {0}.

Category:
Logging

Cause:

Action:

IAM-8030133
Certification creation job stopping just after user selection. Certification Definition: {0}.

Category:
Logging

Cause:

Action:

IAM-8030134
Certification creation job stopping prior to creating certification for certifier: {0}. Certification name: {1}.

Category:
Logging

Cause:

Action:

IAM-8030135
Certification creation job stopping prior to processing batch {0} of {1}. Certification name: {2}.

Category:
Logging

Cause:

Action:

IAM-8030136
Certification creation job stopping prior to persist for batch {0} of {1}. Certification name: {2}.

Category:
Logging

Cause:

Action:

IAM-8030137
Certification creation job stopping just after organization selection. Certification Definition: {0}.

Category:
Logging

Cause:

Action:

IAM-8030138
Certification creation job stopping just after role selection. Certification Definition: {0}.

Category:
Logging

Cause:

Action:

IAM-8030139
Certification creation job stopping just after application instance selection. Certification Definition: {0}.

Category:
Logging

Cause:

Action:

IAM-8030140
Unable to find role with id "{0}" to determine reviewers in role. Certification "{1}" will not be created.

Category:
Logging

Cause:

Action:

IAM-8040001
Encountered error during post-processing of simple user modification event.

Category:
Logging

Cause:

Action:

IAM-8040002
Encountered error during post-processing of bulk user modification event.

Category:
Logging

Cause:

Action:

IAM-8040003
Cannot create event listener "{0}". A listener with the same name already exists.

Category:
Logging

Cause:

Action:

IAM-8040004
Found {0} triggers for a non-existent listener with ruleset name "{1}". Certification will not be created.

Category:
Logging

Cause:

Action:

IAM-8040005
Found {0} triggers for disabled listener "{1}". Certification will not be created.

Category:
Logging

Cause:

Action:

IAM-8040006
Found {0} triggers for listener "{1}", exceeding its maximum of {2}. Certification will not be created.

Category:
Logging

Cause:

Action:

IAM-8040007
All of the triggers for listener "{0}" were filtered out by the certification''s base user selection. Certification will not be created.

Category:
Logging

Cause:

Action:

IAM-8040008
All of the triggers for listener "{0}" were filtered out by the global user IDs for certification "{1}". Certification will not be created.

Category:
Logging

Cause:

Action:

IAM-8040009
Certification for listener "{0}" specifies unsupported selection criteria: criteria type "{1}", search type "{2}". Certification will not be created.

Category:
Logging

Cause:

Action:

IAM-8040010
Listener "{0}" specified an certification type that listeners do not support: "{1}".

Category:
Logging

Cause:

Action:

IAM-8040011
Event listener job interrupted/stopped. Returning without any processing.

Category:
Logging

Cause:

Action:

IAM-8040012
Event listener job interrupted/stopped. Returning before processing rule set: {1}.

Category:
Logging

Cause:

Action:

IAM-8040013
Event listener job interrupted/stopped. Returning before generating any certifications for rule set: {1}.

Category:
Logging

Cause:

Action:

IAM-8040014
Certification Event Trigger Task ran successfully but issued these warnings:

Category:
Logging

Cause:

Action:

IAM-8040015
Triggers for listener "{0}" were processed but did not produce any certifications.

Category:
Logging

Cause:

Action:

IAM-8050001
The logged-in user {0} does not have {1} permission on {2} entity.

Category:
Logging

Cause:

Action:

IAM-8050002
The logged-in user {0} does not have {1} permission on {2} {3} entity.

Category:
Logging

Cause:

Action:

IAM-8050003
The logged-in user {0} does not have permission to access certification task "{1}" because it is assigned to user {2}.

Category:
Logging

Cause:

Action:

IAM-8050004
The logged-in user {0} does not have permission to update certification task "{1}" because it is assigned to user {2}.

Category:
Logging

Cause:

Action:

IAM-8050005
Certification for entity ID {0} not found.

Category:
Logging

Cause:

Action:

IAM-8050006
Certification task corresponding to task UID {0} not found.

Category:
Logging

Cause:

Action:

IAM-8050007
For certification task {0}, caller supplied certification ID ({1}) does not match TaskInfo certification ID ({2}).

Category:
Logging

Cause:

Action:

IAM-8050008
For certification task {0}, logged-in user {1} does not match reviewer login {2}.

Category:
Logging

Cause:

Action:

IAM-8050009
User {0} has access to workflow task UID {1}, but it was assigned to user {2}.

Category:
Logging

Cause:

Action:

IAM-8050010
User {0} is not the certification task reviewer, or the task UID {1} is not active.

Category:
Logging

Cause:

Action:

IAM-8050011
Caught exception during authorization check.

Category:
Logging

Cause:

Action:

IAM-8050012
Unknown certification type: {0}.

Category:
Logging

Cause:

Action:

IAM-8050013
No reference to key {0} of type {1} was found in certification {2} (task {3}).

Category:
Logging

Cause:

Action:

IAM-8050014
The logged user {0} is neither an administrator nor a primary reviewer of certification {1} (ID {2}).

Category:
Logging

Cause:

Action:

IAM-8050015
Authorization advice invoked on unexpected target type: {0}; expected type {1}.

Category:
Logging

Cause:

Action:

IAM-8050016
Authorization advice expected the pointcut method signature first parameter to be of type SearchCriteria; got type {0}.

Category:
Logging

Cause:

Action:

IAM-8050017
Authorization advice expected certification ID (type Long) for first argument; got type {0}.

Category:
Logging

Cause:

Action:

IAM-8050018
Authorization advice expected null or task UID (type String) for second argument; got type {0}.

Category:
Logging

Cause:

Action:

IAM-8050019
Missing subject identifier.

Category:
Logging

Cause:

Action:

IAM-8050020
Missing entity type.

Category:
Logging

Cause:

Action:

IAM-8050021
Missing entity identifier.

Category:
Logging

Cause:

Action:

IAM-8050022
Expected context type {0}; got {1}.

Category:
Logging

Cause:

Action:

IAM-8050023
Expected context subtype {0}; got {1}.

Category:
Logging

Cause:

Action:

IAM-8050024
Invalid context key {0}.

Category:
Logging

Cause:

Action:

IAM-8050025
Certification-based authorization denied for user {0} access to {1} {2} entity, based on certification ID {3} and task UID {4}.

Category:
Logging

Cause:

Action:

IAM-8050026
Invalid certification ID argument {0}.

Category:
Logging

Cause:

Action:

IAM-8050027
Access denied by AuthOPSS authorization service.

Category:
Logging

Cause:

Action:

IAM-8050028
The certification-context bean corresponding to class {0} was not found.

Category:
Logging

Cause:

Action:

IAM-8050029
The Certification instance access authorization check is not performed by CertificationContextResolver.

Category:
Logging

Cause:

Action:

IAM-8050031
Caught exception while converting entity ID to long.

Category:
Logging

Cause:

Action:

IAM-8050032
Certification-based authorization received unexpected entity type {0}.

Category:
Logging

Cause:

Action:

IAM-8050033
Invalid password.

Category:
Logging

Cause:

Action:

IAM-8050034
The password argument must not be null.

Category:
Logging

Cause:

Action:

IAM-8050035
An error occurred while getting the value for system property {0}.

Category:
Logging

Cause:

Action:

IAM-8050036
An error occurred while obtaining the plug-in for plug-in point {0}.

Category:
Logging

Cause:

Action:

IAM-8050038
An error occurred invoking the password verifier plugin.

Category:
Logging

Cause:

Action:

IAM-8050039
The task UID argument must be null.

Category:
Logging

Cause:

Action:

IAM-8060001
Caught exception in CertificationCallback taskExpire method.

Category:
Logging

Cause:

Action:

IAM-8060002
Caught exception in CertificationCallback taskReassign method.

Category:
Logging

Cause:

Action:

IAM-8060003
Caught exception in CertificationCallback taskProxy method.

Category:
Logging

Cause:

Action:

IAM-8060004
Caught exception in CertificationCallback taskReset method.

Category:
Logging

Cause:

Action:

IAM-8060005
Caught exception in CertificationCallback taskComplete method.

Category:
Logging

Cause:

Action:

IAM-8060006
Caught exception in CertificationCallback taskAcquire method.

Category:
Logging

Cause:

Action:

IAM-8100001
IDA scan run aborted: No arguments specified for IDA scan job.

Category:
Logging

Cause:

Action:

IAM-8100002
IDA scan run aborted: No IDA scan definition specified for IDA scan job.

Category:
Logging

Cause:

Action:

IAM-8100003
IDA scan run aborted: IDA scan definition "{0}" was not found.

Category:
Logging

Cause:

Action:

IAM-8100004
IDA scan run stopping before any processing. IDA scan definition: {0}.

Category:
Logging

Cause:

Action:

IAM-8100005
IDA detective scan job with name "{0}" already exists. Please try again with a different name.

Category:
Logging

Cause:

Action:

IAM-8100006
IDA scan run stopping prior to processing batch {0} of {1}. Run name: {2}.

Category:
Logging

Cause:

Action:

IAM-8100007
Requested number of threads exceeds maximum. Maximum will be used. Requested: {0} Max: {1} Scan definition: {2}

Category:
Logging

Cause:

Action:

IAM-8100008
IDA scan run abort. Unable to create ScanRun entity. Scan definition: {0}.

Category:
Logging

Cause:

Action:

IAM-8100009
IDA scan run stopping before all threads started. Attempting immediate shutdown of thread pool. Run name: {0}

Category:
Logging

Cause:

Action:

IAM-8100010
IDA scan run shutdown complete. Run name: {0}

Category:
Logging

Cause:

Action:

IAM-8100011
IDA scan run stopping after all threads started. Attempting immediate shutdown of thread pool. Run name: {0}

Category:
Logging

Cause:

Action:

IAM-8100012
IDA scan run thread pool interrupted. Attempting immediate shutdown. Run name: {0}

Category:
Logging

Cause:

Action:

IAM-8100013
Exception during IDA scan. Run name: {0}. Thread: {1}

Category:
Logging

Cause:

Action:

IAM-8100014
IDA scan run aborted. Unable to find user information for scan creator: {0} Scan definition: {1}

Category:
Logging

Cause:

Action:

IAM-8100015
Requested number of threads is invalid. Number requested: {0} Scan definition: {1}

Category:
Logging

Cause:

Action:

IAM-8100016
IDA scan run errors found. Number of exceptions: {0}

Category:
Logging

Cause:

Action:

IAM-8100017
==> IDA scan run error: {0}

Category:
Logging

Cause:

Action:

IAM-8100018
IDA scan run unable to update status and end time. ScanRun Id: {0} Name: {1} Status: {2}

Category:
Logging

Cause:

Action:

IAM-8100019
Invalid startRow, endRow. startRow: {0} endRow: {1}

Category:
Logging

Cause:

Action:

IAM-8100020
Unable to find ScanRun entity with id: {0}

Category:
Logging

Cause:

Action:

IAM-8100021
IDA scan run. Error during assignment of policy violations. ScanRun Id: {0} Name: {1}

Category:
Logging

Cause:

Action:

IAM-8100022
IDA scan run unable to update user count. Count: {0} Scan run name: {1}

Category:
Logging

Cause:

Action:

IAM-8100023
IDA scan run unable to update violation count. Count: {0} Scan run name: {1}

Category:
Logging

Cause:

Action:

IAM-8100025
IDA scan cleanup job aborted: No arguments specified for IDA scan cleanup job.

Category:
Logging

Cause:

Action:

IAM-8100026
Requested number of threads is invalid. Number requested: {0}

Category:
Logging

Cause:

Action:

IAM-8100027
Requested number of threads exceeds maximum. Maximum will be used. Requested: {0} Max: {1}

Category:
Logging

Cause:

Action:

IAM-8100028
IDA maintenance job aborted: No arguments specified for IDA maintenance job.

Category:
Logging

Cause:

Action:

IAM-8100029
Job stopping after all threads started. Attempting immediate shutdown of thread pool.

Category:
Logging

Cause:

Action:

IAM-8100030
Job shutdown complete.

Category:
Logging

Cause:

Action:

IAM-8100031
Job interrupted after all threads started. Attempting immediate shutdown of thread pool.

Category:
Logging

Cause:

Action:

IAM-8100032
IDA scan cleanup errors found. Number of exceptions: {0}

Category:
Logging

Cause:

Action:

IAM-8100033
==> IDA scan cleanup error: {0}

Category:
Logging

Cause:

Action:

IAM-8100034
IDA Maintenance errors found. Number of exceptions: {0}

Category:
Logging

Cause:

Action:

IAM-8100035
==> IDA Maintenance error: {0}

Category:
Logging

Cause:

Action:

IAM-8100036
No policy violations found for maintenance.

Category:
Logging

Cause:

Action:

IAM-8100037
IDA Maintenance job aborted. Stopping thread {0}

Category:
Logging

Cause:

Action:

IAM-8100038
Exception during IDA Maintenance. Thread: {0}

Category:
Logging

Cause:

Action:

IAM-8100039
IDA scan run unable to update user association, Scan run name: {0}

Category:
Logging

Cause:

Action:

IAM-8100040
Unable to find ScanRun for ScanDefinition cleanup name {0}

Category:
Logging

Cause:

Action:

IAM-8100041
Unable to find ScanDefinition for cleanup name {0}

Category:
Logging

Cause:

Action:

IAM-8100042
Failed to delete scheduled job in cleanup for ScanJob name {0}

Category:
Logging

Cause:

Action:

IAM-8100043
Task context does not contain job details for the cleanup ScanJob

Category:
Logging

Cause:

Action:

IAM-8100044
Task context does not exist for the cleanup ScanJob

Category:
Logging

Cause:

Action:

IAM-8100045
IDA scan run unable to update policy association, Scan run name: {0}

Category:
Logging

Cause:

Action:

IAM-8100046
IDA maintenance job aborted: Workflows are disabled.

Category:
Logging

Cause:

Action:

IAM-8100047
IDA scan run aborted: Workflows are disabled.

Category:
Logging

Cause:

Action:

IAM-8100048
IDA scan cleanup job aborted: Workflows are disabled.

Category:
Logging

Cause:

Action:

IAM-8100050
IDA scan run policy evaluation failed. Run name: {0} Policy ID: {1}

Category:
Logging

Cause:

Action:

IAM-8100051
IDA scan run policy violation submission failed. Run name: {0} Policy ID: {1}

Category:
Logging

Cause:

Action:

IAM-8100052
IDA scan run could not be associated with policy violation. Run name: {0} Policy Violation ID: {1}

Category:
Logging

Cause:

Action:

IAM-8100053
IDA scan run aborted: Could not pre-load policies to be evaluated. Run name: {0}

Category:
Logging

Cause:

Action:

IAM-8100054
IDA scan run completed with no processing. No policies found for evaluation. Run name: {0}

Category:
Logging

Cause:

Action:

IAM-8100055
IDA scan run aborted - Error loading PolicyType. Run name: {0}.

Category:
Logging

Cause:

Action:

IAM-8100056
IDA scan run - Error loading rules for policy. Run name: {0} Policy name: {1} Policy ID: {2}.

Category:
Logging

Cause:

Action:

IAM-8100060
IDA scan argument not provided for {0}.

Category:
Logging

Cause:

Action:

IAM-8100061
{0} length is too large (should be less than 80 characters).

Category:
Logging

Cause:

Action:

IAM-8100070
IDA scan run has completed with errors.

Category:
Logging

Cause:

Action:

IAM-8100071
IDA scan run has completed with warnings.

Category:
Logging

Cause:

Action:

IAM-8100072
IDA scan error in policy remediation specification with {0} for policy {1}

Category:
Logging

Cause:

Action:

IAM-8100073
IDA scan error in user selection criteria. Run name: {0}

Category:
Logging

Cause:

Action:

IAM-8100074
IDA scan error in policy selection criteria. Run name: {0}

Category:
Logging

Cause:

Action:

IAM-8100075
IDA scan warning user selection criteria did not return any users. Run name: {0}

Category:
Logging

Cause:

Action:

IAM-8100077
IDA scan warning catalog evaluation for policies failed. Run name: {0}

Category:
Logging

Cause:

Action:

IAM-8110000
Audit entry was successfully created for Entity Type "{0}", Entity Name "{1}", Entity Id "{2}" and operation {3}

Category:
Logging

Cause:

Action:

IAM-8110001
Audit entry was successfully created for relation between Entity1 type "{0}", Entity1 name "{1}", Entity1 id "{2}" and Entity2 type "{3}", Entity2 name "{4}", Entity2 id "{5}" for operation {6}

Category:
Logging

Cause:

Action:

IAM-8110002
Policy violation cause manager expects all policy violation causes to belong to same policy violation during modify. Policy Violation ID: {0}

Category:
Logging

Cause:

Action:

IAM-8110003
Audit error: Failed to get the data type of attribute {0} for entity {1} due to {2}

Category:
Logging

Cause:

Action:

IAM-8110004
Audit error: Unable to convert CLOB to String.

Category:
Logging

Cause:

Action:

IAM-8110005
Audit Config error: Cannot modify or delete OOTB entity type action.

Category:
Logging

Cause:

Action:

IAM-8110006
Audit Config error: Cannot modify or delete OOTB audit event group.

Category:
Logging

Cause:

Action:

IAM-8110007
Audit Error: Failed to encrypt the hash of the audit event for entity type "{0}", name "{1}", id "{2}" and operation {3}, with error - {4}

Category:
Logging

Cause:

Action:

IAM-8120001
The IDA Configuration property riskAcceptedExpirationLimitInDays must be at least {0,number,integer}.

Category:
Logging

Cause:

Action:

IAM-8130001
Server exception #{0}.

Category:
Logging

Cause:

Action:

IAM-8130002
For more information, search the server"s error log for an entry containing this key: #{0}.

Category:
Logging

Cause:

Action:

IAM-8130003
Server exception occurred during processing of a server exception.

Category:
Logging

Cause:

Action:

IAM-8130101
Following policies failed to be associated with scan run id: "{0}".

Category:
Logging

Cause:

Action:

IAM-8130102
Policy ID: "{0}", Reason: {1}

Category:
Logging

Cause:

Action:

IAM-8130103
IDA entity of type {0} and ID/Name {1} not found

Category:
Logging

Cause:

Action:

IAM-8130104
No users found for policy preview scan

Category:
Logging

Cause:

Action:

IAM-8130105
No Identity Audit policies found for preview scan

Category:
Logging

Cause:

Action:

IAM-8140001
The logged-in user {0} does not have {1} permission on entities of type {2}.

Category:
Logging

Cause:

Action:

IAM-8140002
The logged-in user {0} does not have {1} permission on entity {2} {3}.

Category:
Logging

Cause:

Action:

IAM-8140003
Authorization advice invoked on unexpected target type: {0}; expected type {1}.

Category:
Logging

Cause:

Action:

IAM-8140004
Authorization advice invoked on method {0}: looking for argument {1}, but only {2} argument(s) supplied.

Category:
Logging

Cause:

Action:

IAM-8140005
Authorization advice invoked on method {0}: argument at index {1} is required, but is null.

Category:
Logging

Cause:

Action:

IAM-8140006
Authorization advice invoked on method {0}: argument at index {1} expected runtime type is {2}, but actual runtime type is {3}.

Category:
Logging

Cause:

Action:

IAM-8140007
Action {0}.{1} is not allowed for {2}.{3}.

Category:
Logging

Cause:

Action:

IAM-8140008
Authorization advice invoked on unknown method {0}.{1}.

Category:
Logging

Cause:

Action:

IAM-8140009
Attribute {0} may appear at most once in the SearchCriteria {1}.

Category:
Logging

Cause:

Action:

IAM-8140010
At most one of the attributes {0}, {1}, or {2} may appear in the SearchCriteria {3}.

Category:
Logging

Cause:

Action:

IAM-8140011
Caught exception during authorization check.

Category:
Logging

Cause:

Action:

IAM-8140012
Caught exception during authorization check: checking Remediator for User {0} and PolicyViolation {1}.

Category:
Logging

Cause:

Action:

IAM-8140013
Caught exception during authorization check: checking Remediator for User {0} and PolicyViolationCause {1}.

Category:
Logging

Cause:

Action:

IAM-8140014
Caught exception during authorization check: checking permission to submit request for beneficiary(ies) {0} and targets {1}.

Category:
Logging

Cause:

Action:

IAM-8140015
Caught exception during authorization check: retrieving PolicyViolation IDs for ScanRun ID {0}.

Category:
Logging

Cause:

Action:

IAM-8140016
Caught exception during authorization check: retrieving PolicyViolation IDs available to User {0} via Scan Token {1}.

Category:
Logging

Cause:

Action:

IAM-8140017
Caught exception during authorization check: checking ScanRun {0} creator for User {1}.

Category:
Logging

Cause:

Action:

IAM-8140018
Caught exception during authorization check: checking User {0} access to RequestId {1}.

Category:
Logging

Cause:

Action:

IAM-8140021
At most one of the attributes {0} or {1} may appear in the SearchCriteria {2}.

Category:
Logging

Cause:

Action:

IAM-8140027
Access denied by AuthOPSS authorization service.

Category:
Logging

Cause:

Action:

IAM-8140028
The ida-context bean corresponding to class {0} was not found.

Category:
Logging

Cause:

Action:

IAM-8140029
When search attribute {0} is present, attribute {1} must also be present in the SearchCriteria {2}.

Category:
Logging

Cause:

Action:

IAM-8140030
Caught exception during authorization check: retrieving PolicyViolation entity IDs for User {0} and {1} {2}.

Category:
Logging

Cause:

Action:

IAM-8140032
The scanToken {0} is invalid or the User {1} does not have access to the associated ScanRun entity.

Category:
Logging

Cause:

Action:

IAM-8140033
Caught exception during authorization check: retrieving Request ID {0} for Role {1} (null implies Role creation).

Category:
Logging

Cause:

Action:

IAM-8150001
Error assigning violation remediation task to {0} for policy {1}

Category:
Logging

Cause:

Action:

IAM-8150002
Error closing violation remediation task {0} assigned to {1}

Category:
Logging

Cause:

Action:

IAM-8150003
Error finding Identity Audit Composites of type {0}

Category:
Logging

Cause:

Action:

IAM-8150004
Error assigning violation remediation tasks: {0}

Category:
Logging

Cause:

Action:

IAM-8160001
IDA Scan Definition with name {0} already exists. Please create a definition with a different name.

Category:
Logging

Cause:

Action:

IAM-9070000
The search criteria specified is not valid

Category:
Logging

Cause:

Action:

IAM-9070001
Error occurred while reading plug-in data from the database

Category:
Logging

Cause:

Action:

IAM-9070002
Error occurred while reading jar data from the database

Category:
Logging

Cause:

Action:

IAM-9070003
{0} bytes of data has been generated at the location : {1}

Category:
Logging

Cause:

Action:

IAM-9070004
Caught i/o Exception while writing binary data to file

Category:
Logging

Cause:

Action:

IAM-9070005
Caught sql Exception while writing binary data to file

Category:
Logging

Cause:

Action:

IAM-9070007
An exception occurred while reading the file : {0}

Category:
Logging

Cause:

Action:

IAM-9070008
Platform service is not available

Category:
Logging

Cause:

Action:

IAM-9070009
Exception occurred while importing the data

Category:
Logging

Cause:

Action:

IAM-40302010
The default data for account discriminator field is not populated in definition of access policy (key: {0}) and (name: {1}). Please populate default data.

Category:
Logging

Cause:

Action:

IAM-40302011
The account (key: {0}) for user (key: {1}) is initially provisioned by {2} and not supported for harvesting.

Category:
Logging

Cause:

Action:

IAM-40302012
The Retrofit flag for access policy (key: {0}) and (name: {1}) is set to {2} and hence not considered for linking to account (key: {3}) for user (key: {4}).

Category:
Logging

Cause:

Action:

IAM-40302013
Proceed with access policy harvesting to link Access Policy (name: {0}) to user (key: {1})for account (key: {2})

Category:
Logging

Cause:

Action:

IAM-40600010
An error occurred in {0} while provisioning entitlement with key {1} to user with key {2} in application instance with Key {3} and the cause of error is {4}.

Category:
Logging

Cause:

Action:

IAM-40600011
An error occurred in {0} while fetching entitlement instance with key {1} from orchestration parameters and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-40600012
An error occurred in {0} as entitlement instance with key {1} is not provisioned to user with key {2}.

Category:
Logging

Cause:

Action:

IAM-40600013
An error occurred in {0} as entitlement instance with key {1} is not provisioned to user with key {2}.

Category:
Logging

Cause:

Action:

IAM-40600014
An error occurred in {0} as entitlement instance with key {1} is not provisioned to user with key {2}.

Category:
Logging

Cause:

Action:

IAM-40600015
An error occurred in {0} while revoking entitlement instance with key {1} provisioned to user with key {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-40600016
An error occurred in {0} as parent application instance with key {1} is not available in the request for application instance {2}.

Category:
Logging

Cause:

Action:

IAM-40600018
Provisioning is skipped in {0} as application instance {1} with key {2} is already provisioned to user with key {3}.

Category:
Logging

Cause:

Action:

IAM-40600019
An error occurred in {0} while modifying account with key {1} associated to user with key {2} and the cause of the error is {3}

Category:
Logging

Cause:

Action:

IAM-40610000
Logged in user {0} does not have permission to perform operation {1} on connector server entity.

Category:
Logging

Cause:

Action:

IAM-40610004
Error occured in {0}. Cause of the error is : {1}

Category:
Logging

Cause:

Action:

IAM-40610006
Access denied to logged in user {0} to perform action {1} for target entity type {2} with name {3}.

Category:
Logging

Cause:

Action:

IAM-40611002
Failed to create application objectclass with name {0} due to the following exception {1}

Category:
Logging

Cause:

Action:

IAM-40611003
Successfully created application objectclass with name {0}.

Category:
Logging

Cause:

Action:

IAM-40611004
Created entity of type {0} with name {1}.

Category:
Logging

Cause:

Action:

IAM-40611005
Created child entity of type {0} for parent with id {1}.

Category:
Logging

Cause:

Action:

IAM-40611006
Updated child entity of type {0} for parent with id {1}.

Category:
Logging

Cause:

Action:

IAM-40611007
Deleted child entity of type {0} for parent with id {1}.

Category:
Logging

Cause:

Action:

IAM-40611008
Updated entity of type {0} for with id {1}.

Category:
Logging

Cause:

Action:

IAM-40611009
Deleted entity of type {0} for with id {1}.

Category:
Logging

Cause:

Action:

IAM-40700010
Request Data-set name {0} is not found in MDS.

Category:
Logging

Cause:

Action:

IAM-40700012
Unsupported operator {0}

Category:
Logging

Cause:

Action:

IAM-40700013
Invalid search criteria provided.

Category:
Logging

Cause:

Action:

IAM-40700014
Invalid search criteria field specified {0}.

Category:
Logging

Cause:

Action:

IAM-40700015
No application instance found with application instance key {0}

Category:
Logging

Cause:

Action:

IAM-40700016
No application instance found with application instance name {0}

Category:
Logging

Cause:

Action:

IAM-40700018
Error occurred while adding or updating application instance.

Category:
Logging

Cause:

Action:

IAM-40700019
Error occurred while performing application instance soft-delete.

Category:
Logging

Cause:

Action:

IAM-40700020
No displayname specified for application instance {0}

Category:
Logging

Cause:

Action:

IAM-40700021
No process form exists for {0}

Category:
Logging

Cause:

Action:

IAM-40700022
Multiple process forms exist for {0}

Category:
Logging

Cause:

Action:

IAM-40700023
An error occurred in {0} as resource with name {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-40700024
An error occurred in {0} while finding resource with name {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-40700025
An error occurred in {0} while finding the process form details for the resource with name {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-40700028
An error occurred in {0} as parent process form with name {1} does not exist.

Category:
Logging

Cause:

Action:

IAM-40700029
An error occurred in {0} while finding parent process form with key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-40700030
An error occurred in {0} while finding the child form details for the parent form with key {1} and the cause of error is {2}.

Category:
Logging

Cause:

Action:

IAM-40700031
An error occurred in {0} as form with key {1} and version {2} is not found.

Category:
Logging

Cause:

Action:

IAM-40700032
An error occurred in {0} as multiple forms found with key {1} and version {2}.

Category:
Logging

Cause:

Action:

IAM-40700033
An error occurred in {0} while finding form details for a form with key {1} and version {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-40700034
An error occurred in {0} while finding form details for a form with key {1} and version {2} and the cause of error is {3}.

Category:
Logging

Cause:

Action:

IAM-90400044
An error occurred in {0} and the cause of error is {1}.

Category:
Logging

Cause:

Action:

IAM-90400083
An error occurred in {0} while getting parent form details for process instance {1} as the parent form does not have details for the specified process instance.

Category:
Logging

Cause:

Action:

IAM-90400084
An error occurred in {0} while scheduling bulk insert task for child table {1}.

Category:
Logging

Cause:

Action:

14
IAU-01023 to IAU-62023

IAU-01023
Invalid filter preset. The Valid choices are {0}

Category:
Other

Cause:
The given audit level(filter preset) is invalid.

Action:
Give a valid audit level(filter preset) like Low,Medium,None,Custom.

IAU-01024
Max Dir Size should be atleast double that of min File Size and min File Size should be 4K

Category:
Other

Cause:
Error in setting the maximum directory size or file size for audit logs.

Action:
Give a valid value for maximum directory and file size.

IAU-01025
Unknown componentType {0} at character position:{1}

Category:
Other

Cause:
The component type given in custom event expression is invalid.

Action:
Enter valid component type. listAuditEvents() command gives a list of component types.

IAU-01026
Invalid Event Name: {0}

Category:
Other

Cause:
The event name in custom event expression is invalid.

Action:
Enter valid event name. listAuditEvents() command gives a list of all the events for a given component.

IAU-01027
Invalid component Type: {0}

Category:
Other

Cause:
The component type given in custom event expression is invalid.

Action:
Give valid component type.listAuditEvents() command gives a list of component types.

IAU-01028
Can't read components_dir {0}

Category:
Other

Cause:
Install is possibly corrupted.

Action:
Check your install and contact Oracle Customer Support.

IAU-01029
User {0} not found

Category:
Other

Cause:
The user to be removed is not in the list of special users(users to always audit).

Action:
Check for the list of special users(users to always audit)already present using getAuditPolicy() command.

IAU-01030
Unknown construct . expecting eventName at character position:{0}

Category:
Other

Cause:
Invalid syntax in custom event expression.

Action:
Event name is expected at that position.

IAU-01031
Unknown event {0} at character position:{1}

Category:
Other

Cause:
Invalid event in custom event expression.

Action:
Enter a valid event name. listAuditEvents() command gives a list of all the events for a given component.

IAU-01032
Expecting SUCCESSESONLY or FAILURESONLY after the dot at charcter position:{0}

Category:
Other

Cause:
Invalid syntax in custom event expression.

Action:
The events name should be qualified with either SUCCESSONLY or FAILURESONLY after the dot.

IAU-01033
Unknown construct . expecting componentType at character position {0}

Category:
Other

Cause:
componentType is expected at that position.

Action:
Enter valid component type.listAuditEvents() command gives a list of component types.

IAU-01034
Component type {0} is repeated at character position:{1}

Category:
Other

Cause:
Invalid syntax in custom event expression.

Action:
Specify a component exactly once giving the list of all events to be added or removed.

IAU-01035
Missing character after backslash at character position:{0}

Category:
Other

Cause:
The string at the specified position is invalid.

Action:
Remove the trailing backslash.

IAU-01036
Unterminated quoted string at character position:{0}

Category:
Other

Cause:
No matching end quote in the string.

Action:
Check the specified string and add the matching end quote.

IAU-01037
custom events can only be specified for custom filter preset

Category:
Other

Cause:
Custom events are added when the audit level(filter preset) is not Custom.

Action:
Change the audit level(filter preset) to Custom.

IAU-01038
Unexpected token {0} found at character position {1}

Category:
Other

Cause:
Invalid syntax in custom events expression.

Action:
Check the custom events expression given.

IAU-01039
Unfinished string that started at position {0}

Category:
Other

Cause:
Custom event expression string is not terminated.

Action:
Check the string and terminate it.

IAU-01040
Unrecognized token at position {0}

Category:
Other

Cause:
Invalid syntax in custom events expression.

Action:
Check for the syntax of custom events expression.

IAU-01041
Expecting RHS for the boolean operator {0} at position {1}

Category:
Other

Cause:
Invalid syntax in custom event expression.

Action:
Give a RHS value for the boolean operator to evaluate.

IAU-01042
Unexpected token {0} found. Expecting -and or -or or ')' at position {1}

Category:
Other

Cause:
Invalid syntax in custom events expression.

Action:
Check for the syntax of custom events expression.

IAU-01043
Expecting ')' corresponding to '(' at {0}

Category:
Other

Cause:
There is no matching end brace in custom events expression string.

Action:
Check the expression and add a closing brace at the end to match with the beginning brace.

IAU-01044
Expecting a relation expression at position {0}

Category:
Other

Cause:
Invalid syntax in custom events expression.

Action:
Check for the syntax of custom events expression.

IAU-01045
Operator {0} is not applicable for an attribute of type {1} at position {2}

Category:
Other

Cause:
Invalid operator given for an attribute in custom events expression.

Action:
Use an operator that is allowed to be used with the attribute.

IAU-01046
Invalid boolean operator {0}

Category:
Other

Cause:
Invalid syntax in custom events expression.

Action:
Give a valid boolean operator.

IAU-01047
Attribute {0} needs a string at position {1}

Category:
Other

Cause:
The value given for the attribute is not a string.

Action:
Give a string value in double quotes.

IAU-01048
Attribute {0} needs a boolean at position {1}

Category:
Other

Cause:
The value given for the attribute in custom events expression is of a different type.

Action:
Give a boolean value(true or false) for this attribute.

IAU-01049
Attribute {0} needs a number at position {1}

Category:
Other

Cause:
The value given for the attribute in custom events expression is of a different type.

Action:
Give a number value for this attribute.

IAU-01050
Attribute {0} needs a date at position {1}

Category:
Other

Cause:
The value given for the attribute in custom events expression is of a different type.

Action:
Give a date value for this attribute.

IAU-01051
Cannot parse {0} into a date. Error {1} at {2}

Category:
Other

Cause:
Date value entered is invalid.

Action:
Give a valid date value.

IAU-01052
Unparseable date {0} at position {1}

Category:
Other

Cause:
Date value entered is invalid.

Action:
Give a valid date value.

IAU-01053
Unparseable time {0} at position {1}

Category:
Other

Cause:
Invalid time given in the custom events expression.

Action:
Enter valid time format.

IAU-01054
Error in expression: unknown operator

Category:
Other

Cause:
Invalid operator given in a custom events expression.

Action:
Give a valid operator.

IAU-01055
Expecting a Boolean value for attrib:{0}

Category:
Other

Cause:
The value given for the attribute in custom events expression is of a different type.

Action:
Give a boolean value for the attribute.

IAU-01056
Expecting a Number value for attrib:{0}

Category:
Other

Cause:
The value given for the attribute in custom events expression is of a different type.

Action:
Give a number value for the attribute.

IAU-01057
No relational expressions allowed for Binary operator

Category:
Other

Cause:
Binary attribute is present in the custom events expression.

Action:
Remove binary attribute from the custom events expression.

IAU-01058
Expecting a Date value for attrib:{0}

Category:
Other

Cause:
A non-date value is given to the date attribute.

Action:
Give a date value for the attribute.

IAU-01059
trailing backslash in special users

Category:
Other

Cause:
Invalid special users(Users to always audit) string.

Action:
Remove the trailing back slash in special users(Users to always audit)string.

IAU-01060
Invalid config file

Category:
Other

Cause:
Config file given in importAuditConfig() command is possibly corrupted.

Action:
Contact Oracle Customer Support.

IAU-1061
Dynamic audit store is not configured

Category:
Other

Cause:
The setup is not configured to use Audit Store

Action:
Read the documentation and configure audit store

IAU-01062
Audit Registration Service is not available

Category:
Other

Cause:
Component audit registration failed

Action:
There could be something wrong with the component audit event definition. Check the diagnostic logs for more information

IAU-1063
Either a component event definition file or the compoentType has not been provided

Category:
Other

Cause:
Component event definition file is missing or the compoentType has not been provided

Action:
Provide a componentType and the component event definition file

IAU-1064
AuditLoader Configuration Initialized with Unsupported Timezone {0}. Defaulting to UTC

Category:
Other

Cause:
Unsupported timezone property value is used

Action:
Use a supported timezone value. Supported values are local and utc

IAU-1065
Event(s) {0} exists in audit policy for component type {1}

Category:
Other

Cause:
Events being added already exists in the Custom Event list for the component

Action:
Remove duplicate events from the events that are being added to the Custom event list

IAU-1066
Event(s) {0} not found in audit policy for component type {1}

Category:
Other

Cause:
Events being removed do not exist in the Custom Event list for the component

Action:
Do not try to remove events that do not exist in the Custom Event list

IAU-1067
ComponentType should not be passed in for System Components

Category:
Other

Cause:
Passing in the componentType as one of the params for audit WLST commands is not supported for system components

Action:
Do not pass in the componentType for non JEE/JSE components

IAU-1068
Problem retrieving System Component Attributes from audit store

Category:
Other

Cause:
There is something wrong with the audit store

Action:
Check the diagnostic logs for more information

IAU-1069
Environment variables COMMON_COMPONENTS_HOME or {0} or {1} is not set to read Events

Category:
Other

Cause:
Environment variable COMMON_COMPONENTS_HOME is not set

Action:
Set the value for COMMON_COMPONENTS_HOME

IAU-1070
Cannot start the audit loader thread. Error in executor service retrieval

Category:
Other

Cause:
Executor service retrieval failed

Action:
Check the diagnostic logs for more information

IAU-1071
Cannot change the repository type from DB to File. Valid value for switchToDB switch is true

Category:
Other

Cause:
The value for switchToDB in setAuditRepository WLST command was set to false

Action:
We cannot change the repositoryType from Db to File

IAU-1072
Cannot change the interval value to {0}, Valid value for interval switch is positive numeric

Category:
Other

Cause:
The interval value for audit loader is not valid

Action:
Pass in a valid value for audit loader interval

IAU-1073
Cannot change the timezone value to {0}, Valid value for timezone switch is local or utc

Category:
Other

Cause:
The timezone value is invalid.

Action:
Give a valid timezone value

IAU-1074
Audit Repository Information updated

Category:
Other

Cause:
The audit config has been updated with the audit repository information

Action:
None

IAU-1075
Operation is not supported. componentType needs to be passed in

Category:
Other

Cause:
The operation failed because the componentType was not provided

Action:
Provide the componentType

IAU-1076
Cannot create IAU Audit DB View. Invalid View Type {0}

Category:
Other

Cause:
Invalid view type has been provided

Action:
Provide a valid view type for creating the IAU Audit DB view

IAU-1077
Cannot create Indexable IAU Audit DB View. No indexable used attributes found in definition for componentType {0}

Category:
Other

Cause:
Indexable attributes not found in component audit definition

Action:
Provide indexable attributes in component audit definition

IAU-1078
Cannot create Indexable IAU Audit DB View. No mappings found for NS {0}

Category:
Other

Cause:
No attribute data mappings found for component

Action:
Check if the component audit registration was successful in the diagnostic logs

IAU-1079
There is no data mapping for the component type passed {0}

Category:
Other

Cause:
Component audit registration could have been unsuccessful

Action:
Check the diagnostic logs for more information

IAU-1080
Audit Store passed is null

Category:
Other

Cause:
Audit Store failure

Action:
Check the diagnostic logs for more information

IAU-1081
Audit Data DB Type {0} is not supported for {1} IAU view

Category:
Other

Cause:
Some other DB type other than Oracle was provided

Action:
Provide Oracle as the DB type

IAU-1082
Couldn't retrieve connected user from datasource. Grants may fail

Category:
Other

Cause:
Database access failed

Action:
Check the diagnostic logs for more information

IAU-1083
Couldn't create Indexable IAU Audit DB View for component {0}

Category:
Other

Cause:
Failure during the creation of Indexable Audit Database view

Action:
Check the diagnostic logs for more information

IAU-1084
No Definitions found for component {0} in audit store

Category:
Other

Cause:
Component is not registered in the audit store

Action:
Register the component in audit store

IAU-1085
Successfully Created IAU View {1} for component {0}

Category:
Other

Cause:
IAU view has been created for the component

Action:
None

IAU-1086
Could not Create IAU View for component {0}

Category:
Other

Cause:
Creation of audit view failed for component

Action:
Check if view creation is disabled or if there is some issue with the indexable/simple view creation. Check diagnostic logs for more information

IAU-1087
Couldn't generate SQL. Only Oracle Database is supported for Indexable IAU view

Category:
Other

Cause:
Generation of indexable view creation script failed

Action:
Check if the appropriate DB type is passed in. Only Oracle database is supported

IAU-05011
Audit Loader initialization failed. The Audit loader is disabled. Caught Exception {0}

Category:
Other

Cause:
An error prevented the Audit Loader from starting.

Action:
Check the diagnostic logs and contact Oracle Customer Support.

IAU-05042
Error in reading component definition from {0}

Category:
Other

Cause:
Install might be corrupted.

Action:
Check the install and contact Oracle Customer Support.

IAU-05043
Cannot create directory for saving AuditLoader state {0}

Category:
Other

Cause:
OS error in creating directory.

Action:
Check file permissions and disk space.

IAU-05044
Cannot save AuditLoader state to file {0}

Category:
Other

Cause:
OS error in writing to state file.

Action:
Check file permissions and disk space.

IAU-05045
Cannot read AuditLoader state from file {0}

Category:
Other

Cause:
OS error in reading state file.

Action:
Check file permissions or the file is possibly corrupted.

IAU-05046
Stopping AuditLoader, caught exception: {0}

Category:
Other

Cause:
An error prevented Audit Loader from continuing.

Action:
Check the diagnostic logs and contact Oracle Customer Support.

IAU-05047
Problem in transferring audit record from file:{0} position:{1} will retry in next cycle. caught exception {2}

Category:
Other

Cause:
The database containing Audit store is probably down.

Action:
Check the database availability. Restart the database if required.

IAU-05048
Problem in transferring audit record to Repository {0}. Please verify your Repository Configuration

Category:
Other

Cause:
The database configuration is invalid or the database is down.

Action:
Check Audit Store configuration and bring up the database if it is down.

IAU-5049
Unable to create Data Source for connection string {0} and DB user {1}

Category:
Other

Cause:
Creation of data source failed. The connection string or the DB user value could be wrong.

Action:
Check if the connection string and DB user values are correct

IAU-5050
Unable to close data source

Category:
Other

Cause:
Failed to close data source

Action:
Check diagnostic logs for more information

IAU-5051
Unable to get a database connection with connect string {0}

Category:
Other

Cause:
Failed to get database connection. The connection string used to connect to the database could be wrong.

Action:
Check if the connection string value is correct

IAU-5052
JNDI resource does not exist for JNDI name {0}

Category:
Other

Cause:
There is no corresponding JNDI resource for the JNDI name specified

Action:
Check if the JNDI resource exists or the correct JNDI name was used

IAU-5053
Unable to get a connection from the data source for JNDI name {0}

Category:
Other

Cause:
Database access failed

Action:
Check if the datasource for the JNDI name exists and if the correct JNDI name is used

IAU-5054
Problem in getting Audit Service, caught exception: {0}

Category:
Other

Cause:
Error in getting the audit service.

Action:
Check the diagnostic logs for more information

IAU-5055
Properties {0}, {1} and {2} should be defined in the audit service properties

Category:
Other

Cause:
Required properties do not have values set

Action:
Set valid property values for required properties

IAU-5056
Unable to determine the audit log directory. Either the audit service property {0} or system properties {1}, {2} have not been provided

Category:
Other

Cause:
Audit log directory location has not been set

Action:
Set the audit log directory value for the audit.logDirectory service property or use the system property to set the audit log directory. Refer to the OPSS Audit section in Oracle documentation

IAU-5057
Cannot create state file for saving AuditLoader state. Base directory is not set.

Category:
Other

Cause:
Audit log directory location has not been set

Action:
Set the audit log directory value for the audit.logDirectory service property or use the system property to set the audit log directory. Refer to Oracle documentation for more information

IAU-06001
Error in reading audit configuration file from {0}.

Category:
Other

Cause:
Install might be corrupted.

Action:
Check the install and contact Oracle Customer Support.

IAU-06002
Invalid {0} directory: {1}.

Category:
Other

Cause:
Invalid directory path.

Action:
Check that the directory path is valid and the directory is writable.

IAU-06003
Cannot create directory: {0}.

Category:
Other

Cause:
Unable to create directory.

Action:
Check the directory path is valid and the directory is writable.

IAU-06004
Cannot write to {0}: {1}.

Category:
Other

Cause:
Unable to create directory.

Action:
Check the directory path is valid and the directory is writable.

IAU-06005
Denied access to log directory: {0}.

Category:
Other

Cause:
Unable to read/write from/to directory

Action:
Check the directory path is valid and the directory is writable.

IAU-06006
Error in parsing audit component events definition from {0}.

Category:
Other

Cause:
Audit configuration file is possibly corrupted.

Action:
Check the diagnostic logs and contact Oracle Customer Support.

IAU-06007
Failed while reloading audit configuration.

Category:
Other

Cause:
Audit configuration file is possibly corrupted.

Action:
Check the diagnostic logs and contact Oracle Customer Support.

IAU-06008
Error while evaluating event auditability.

Category:
Other

Cause:
Audit configuration file is possibly corrupted.

Action:
Check the diagnostic logs and contact Oracle Customer Support.

IAU-06009
Failed to log audit event.

Category:
Other

Cause:
Error in loading audit configuration or writing to audit logs.

Action:
Check the diagnostic logs and contact Oracle Customer Support.

IAU-6010
"Error while reading release version from audit log file {0} : {1}

Category:
Other

Cause:
Audit log file is not present

Action:
Check the diagnostic logs for more information

IAU-6011
Failed to log busstop header

Category:
Other

Cause:
OS error while writing to the audit log file

Action:
Check file permissions and disk space. Also, check the diagnostic logs for more information

IAU-6012
Unable to determine the audit log directory. No log directory specified

Category:
Other

Cause:
Audit log directory location is not set

Action:
Check the diagnostic logs for more infomation

IAU-6013
Error in audit channel for component {0}. Cannot write audit records. Check if audit log directory is set.

Category:
Other

Cause:
Audit log directory location is not set

Action:
Check the diagnostic logs for more infomation

IAU-6014
Duplicated audit entry : {0} exists in componentType {1}

Category:
Other

Cause:
Duplicate entry in component audit definition

Action:
Remove the duplicate entry from the component audit definition

IAU-62003
parsing of component_events.xml file failed

Category:
Other

Cause:
Install is possibly corrupted.

Action:
Check the install. Contact Oracle Customer Support if needed.

IAU-62004
parsing of auditconfig.xml file failed

Category:
Other

Cause:
Install is possibly corrupted.

Action:
Check the install. Contact Oracle Customer Support if needed.

IAU-62005
parsing of generic_events.xml file failed

Category:
Other

Cause:
Install is possibly corrupted.

Action:
Check the install. Contact Oracle Customer Support if needed.

IAU-62006
ORACLE_HOME environment variable not set

Category:
Other

Cause:
The environment variable ORACLE_HOME was not set.

Action:
Set the ORACLE_HOME environment variable.

IAU-62007
COMPONENT_CONFIG_PATH environment variable not set

Category:
Other

Cause:
The environment variable COMPONENT_CONFIG_PATH was not set.

Action:
Set the COMPONENT_CONFIG_PATH to point to the location of the auditconfig.xml file.

IAU-62008
ORACLE_INSTANCE environment variable not set

Category:
Other

Cause:
The environment variable ORACLE_INSTANCE was not set.

Action:
Set the ORACLE_INSTANCE environment variable.

IAU-62009
COMPONENT_NAME environment variable not set

Category:
Other

Cause:
The COMPONENT_NAME environment variable was neither set nor was the component_events.xml file present in the expected default location.

Action:
Check if the component_events.xml file is present in the expected default location or set the COMPONENT_NAME environment variable to point to the correct component name.

IAU-62010
COMPONENT_TYPE environment variable was not set

Category:
Other

Cause:
The COMPONENT_TYPE environment variable was neither set nor was the component_events.xml file present in the expected default location.

Action:
Check if the component_events.xml file is present in the expected default location or set the COMPONENT_TYPE environment variable to point to the correct component type.

IAU-62012
audit event creation failed

Category:
Other

Cause:
The creation of the audit event failed.

Action:
Contact Oracle Customer Support.

IAU-62015
audit custom expression parsing failed

Category:
Other

Cause:
Parsing of the custom expression had failed.

Action:
Check if the custom expression used in the audit configuration is valid.

IAU-62016
audit log file creation failed

Category:
Other

Cause:
OS error in creating the file.

Action:
Check file permissions and disk space.

IAU-62018
timestamp error

Category:
Other

Cause:
There was a problem with getting the current date and time.

Action:
Check the diagnostic logs and contact Oracle Customer Support.

IAU-62019
audit enabled check failed

Category:
Other

Cause:
Invalid values assgined to audit event attributes.

Action:
Check the diagnostic logs and contact Oracle Customer Support.

IAU-62021
busstop open failed

Category:
Other

Cause:
OS error in creating or opening the bus-stop file.

Action:
Check the file permissions and disk space.

IAU-62023
audit config reload failed

Category:
Other

Cause:
There was a problem in reloading the audit config data that has been modified.

Action:
Check the diagnostic logs and contact Oracle Customer Support.

15
INST-01000 to INST-10117

INST-01000
Internal Error: Undefined module found: {0}.

Category:
Installation

Cause:
The module {0} present in engineConfig.xml is undefined.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01001
Abnormal Program Termination.

Category:
Installation

Cause:
The program has experienced an error for some internal or unexpected reason.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01002
Error: Undefined flag: {0}.

Category:
Installation

Cause:
The flag {0} specified on the command line is not supported.

Action:
Refer to the usage: setup.exe -help

INST-01003
Error: Response file not specified.

Category:
Installation

Cause:
A response file must be provided when installing in the {0} mode.

Action:
Specify a valid response file. Usage: setup.exe -s -response <Full path to response file>

INST-01004
Internal Error: File not found: {0}.

Category:
Installation

Cause:
Page data definition {0} for page {1} not found.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01005
Internal Error: Multiple pages found with "{0}" attribute set to true.

Category:
Installation

Cause:
There can be only one page with {0} attribute set to true.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01006
Internal Error: No page found with the "{0}" attribute set to true.

Category:
Installation

Cause:
At least one page must have the "{0}" attribute set to true.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01007
Error: Invalid input: "{0}"

Category:
Installation

Cause:
This error is caused due to invalid input on the command line

Action:
Refer to the command line usage.

INST-01008
Internal Error: Operation not specified

Category:
Installation

Cause:
Engine did not find an operation to run in this configuration.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01009
Error: Invalid flags specified for operation "{0}": "{1}"

Category:
Installation

Cause:
Flags specified by the user on the command line are not supported for this operation:{0}

Action:
Refer to the command line usage.

INST-01010
Internal Error: Parse error:{0}

Category:
Installation

Cause:
A parse error occurred. The file:"{0}" is not in proper format.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01011
Internal Error: More than one incompatible operation specified: "{0}", "{1}"

Category:
Installation

Cause:
Incompatible operation specified

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01012
Internal Error: More than one incompatible mode is specified at a time: "{0}", "{1}"

Category:
Installation

Cause:
Incompatible modes specified

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01013
Internal Error: Default mode not specified for operation:{0}

Category:
Installation

Cause:
Default mode not specified

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01014
Internal Error: Default Operation not specified.

Category:
Installation

Cause:
Default Operation not specified

Action:
Contact Oracle Support Services with these log files {0}\n{1}.

INST-01015
Internal Error: Found cyclic references to page: "{0}". Verify file: "{1}".

Category:
Installation

Cause:
Cyclic references to other pages were found in the page data file: {0}

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01016
Internal Error: Multiple references of page: "{0}" found in the "{1}" section for page: "{2}"

Category:
Installation

Cause:
Multiple next page references are not supported by the Oracle Install Engine.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01017
Internal Error: The following pages do not have a default next page specified: "{0}"

Category:
Installation

Cause:
Default Next Page is mandatory for each page.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01018
Internal Error: Duplicate definition found for pages: "{0}".

Category:
Installation

Cause:
Duplicate definition of pages detected.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01019
Internal Error: Next page sequence not specified for the following pages: "{0}".

Category:
Installation

Cause:
In cases where multiple next pages follow this page, next page sequence is mandatory to define the page flow.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01020
Internal Error: Page definition not found for: "{0}".

Category:
Installation

Cause:
Each Page should be accompanied by its page definition in the page data file.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01021
Internal Error: Page name not specified for file: "{0}".

Category:
Installation

Cause:
Page name not specified

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01022
Internal Error: Page name mismatch. Names specified: "{0}" and "{1}".

Category:
Installation

Cause:
Page name mismatch

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01023
Internal Error: Unable to provide usage

Category:
Installation

Cause:
No usage available for this option: {0}. For more help refer this to Oracle Support Services.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01024
Invalid checkpoint file: {0}.

Category:
Installation

Cause:
The existing checkpoint file is not in the correct format.

Action:
Delete the invalid checkpoint file:{0}

INST-01025
Invalid checkpoint file: {0}. The release and/or version of the product in the checkpoint does not match the current product. {1}.

Category:
Installation

Cause:
Not a valid checkpoint file for the current release/version.

Action:
Delete the invalid checkpoint file

INST-01026
Response File parse error at Line no: {0} - {1}

Category:
Installation

Cause:
The response file may be corrupted or has errors

Action:
Correct the errors in the response file and try the install operation again.\nCheck if you have missed specifying square brackets around the section names

INST-01027
Section name cannot be empty and should be enclosed in square brackets.

Category:
Installation

Cause:
The Response File is not a valid response file. The Section Name is not specified or is not specified properly.

Action:
The Response Files are organized into 4 sections namely ENGINE, GENERIC, SYSTEM AND APPLICATIONS. \nEach Section Should be enclosed in square brackets and appropriate entries should be specified under them (Example: [Generic]). Check the Section Names.

INST-01028
Error: No Section defined.

Category:
Installation

Cause:
The Response File does not have any valid sections specified. The Response File is organized into 4 sections namely ENGINE, GENERIC, SYSTEM and APPLICATIONS.\nAll Section Names are specified within square brackets.

Action:
Verify the Specified Response Files for valid Section Names and Syntaxes

INST-01029
Response File Parse Error : No Equal Symbol "=" was found

Category:
Installation

Cause:
The Format of specifying the value for a variable inside the response file is as VARIABLE_NAME=VALUE. The Equal Symbol "=" was missed

Action:
Correct the Response File to specify the value for a variable as VARIABLE_NAME=VALUE. Insert the Equal Symbol "=" in appropriate position to correct the same

INST-01030
Response File Parse Error

Category:
Installation

Cause:
The Variable {0} was not Found in the Response File

Action:
Specify the Variable in the Response File. The Syntax of specifying a variable is as VARIABLE_NAME=VALUE

INST-01031
Response File Parse Warning. No value found. Ignoring.

Category:
Installation

Cause:
The Variable {0} was found in the Response File with no value assigned to it and hence it was ignored while the Response File was Parsed.

Action:
Specify the corresponding value.

INST-01032
Internal Error: Unable to create the Configuration Manager.

Category:
Installation

Cause:
Configuration Files are not proper\n:{0}

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01033
Internal Error: Fatal Error Occurred while loading Configuration Actions.

Category:
Installation

Cause:
Configuration Action Locations specified are incorrect\n:{0}

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01034
Internal Error: Fatal Error Occurred while publishing Configuration Actions.

Category:
Installation

Cause:
Configuration Actions are improper\n:{0}

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01035
Internal Error: Fatal Error Occurred while loading Configuration Actions.

Category:
Installation

Cause:
Configuration Actions are improper\n:{0}

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01036
Internal Error: Fatal Error Occurred while setting data for Configuration Actions.

Category:
Installation

Cause:
Variable: {0} required by Action: {1} not found.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01037
Internal Error: Fatal Error Occurred while initializing data for Configuration Action.

Category:
Installation

Cause:
Variable: {0} required by Action: {1} not initialized.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01038
Internal Error: Fatal Error Occurred while loading Configuration Action:{0}.

Category:
Installation

Cause:
Class: {0} not found.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01039
Internal Error: Fatal Error Occurred while running lifecycle methods for Configuration Actions.

Category:
Installation

Cause:
Lifecycle Error

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01040
Internal Error: There was an error while copying files to this location: {0}.\n Installation cannot continue.

Category:
Installation

Cause:
Error in copying files

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01041
Response File Location:{0} is not readable.

Category:
Installation

Cause:
Response File does not exist or does not have read permission. Response File path contains special characters.

Action:
Ensure that the response file exists and is readable. The response file path must not contain any special characters.\nOnly Alphanumeric, _, dot, and space characters are allowed.

INST-01042
An error occurred while reading the response file.

Category:
Installation

Cause:
Response File does not exist at the specified location. Response file is not in the correct format.

Action:
Ensure that the response file exists. Ensure that the Response File is in the correct format. The Response Files are organized into 4 sections namely ENGINE, GENERIC, SYSTEM AND APPLICATIONS.\nEach Section Should be enclosed in square brackets and appropriate entries should be specified under them.

INST-01043
Internal Error: Response File location not defined.

Category:
Installation

Cause:
The file location provided to the writer is empty.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01044
Response File Location: {0} is not writable.

Category:
Installation

Cause:
The specified file already exists or user does not have write permission in the given location. Response File path contains special characters.

Action:
Ensure that the response file location is writable. The response file path must not contain any special characters.\nOnly Alphanumeric,_,dot and space characters are allowed.

INST-01045
Response File Parse Error: Section Name "{0}" is invalid.

Category:
Installation

Cause:
Section "{0}" does not exist.

Action:
Ensure that the Section name is one of the following 1. ENGINE 2. GENERIC 3. SYSTEM 4. APPLICATIONS

INST-01046
Internal Error: Invalid Install Session.

Category:
Installation

Cause:
Data Model is empty.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01047
Silent Install cannot continue, error {0}.

Category:
Installation

Cause:
Data provided in the response file is insufficient to complete this installation. Data provided in the response file is incorrect and did not pass all the validations.

Action:
Fill the indicated information in the response file and restart installation. Verify and change the indicated values specified in the response file and restart installation.

INST-01048
Internal Error: Aborting Silent Install.

Category:
Installation

Cause:
Error while running silent install

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01049
There was a problem in creating the page sequence. Response File Data is incomplete.\nError: {0}

Category:
Installation

Cause:
Data provided in the response file is insufficient to complete this installation.

Action:
Fill the indicated information in the response file and restart installation.

INST-01050
Some required prerequisites for this installation have failed. Installation cannot continue

Category:
Installation

Cause:
Response File does not exist at the specified location. Response file is not in the correct format.

Action:
Ensure that the response file exists. Ensure that the Response File is in the correct format. The Response Files are organized into 4 sections namely ENGINE, GENERIC, SYSTEM AND APPLICATIONS.\nEach Section Should be enclosed in square brackets and appropriate entries should be specified under them.

INST-01051
Some required prerequisites for this installation have failed. Installation cannot continue

Category:
Installation

Cause:
Failed Prerequisite: {0}

Action:
Take a look at the failed prerequisites and fix the necessary items. Restart the installation after you are done.

INST-01052
Error: Property: {0} does not belong to the Section: {1}. It will be ignored.

Category:
Installation

Cause:
All variables in the response files are associated with a valid section. The variable specified in the response file does not belong to the section it appears in.

Action:
Check if the variable is actually a valid property name and is present in the appropriate section.

INST-01053
[CONFIG]:: ACTION: {0} running.

Category:
Installation

Cause:

Action:

INST-01054
[CONFIG]:: STEP {0} running.

Category:
Installation

Cause:

Action:

INST-01055
Configuration Directory:{0} does not exist.

Category:
Installation

Cause:

Action:

INST-01056
The file:{0} cannot be loaded as a configuration action.

Category:
Installation

Cause:
The Configuration framework loads the configuration actions from jars or xml files. This file does not represent a configuration action.

Action:
Correct the file and retry

INST-01057
Invalid Log level: {0} specified.

Category:
Installation

Cause:
Log levels that can be specified on the command line can be: INFO, ERROR, DEBUG

Action:
Specify a valid log level.

INST-01058
Log level changed to: {0}

Category:
Installation

Cause:

Action:

INST-01059
Following checks will be retried by the Prerequisites checker:\n{0}

Category:
Installation

Cause:

Action:

INST-01060
Error: Prerequisite check: {0} has failed.

Category:
Installation

Cause:
Prerequisite check: {0} has failed

Action:
Correct the failed prerequisite and retry

INST-01061
Warning: An optional Prerequisite check: {0} has failed.

Category:
Installation

Cause:

Action:

INST-01062
Invalid Inventory Pointer location: {0} specified on the command line.

Category:
Installation

Cause:
Inventory pointer file does not exist. Directory specified for the inventory cannot be created.

Action:
Create a valid inventory pointer file at the location which is specified on the command line. Inventory pointer file is a property file containing two entries\ninventory_loc=<Directory where new inventory is present or to be created>\nGROUP=<group of the installing user>

INST-01063
Invalid inventory location:{0}.

Category:
Installation

Cause:
Directory specified for the inventory cannot be created.

Action:
Provide a writable directory for the inventory.

INST-01064
Oracle home value was not set by the Installer.

Category:
Installation

Cause:
Required Oracle home value not set

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01065
Library: {0} required for Action: {1} not found.

Category:
Installation

Cause:
Required library not found

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01066
Configuration Data Store not found.

Category:
Installation

Cause:
Required Configuration Data Store not found

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01067
Error while loading Configuration Actions from file: {0}

Category:
Installation

Cause:
Problem while loading the configuration actions

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01068
No configurations defined for this installation.

Category:
Installation

Cause:

Action:

INST-01069
Internal Error: Unable to load Configuration Action: {0}

Category:
Installation

Cause:
Class not found: {0}

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-01070
Internal Error: Entry Point for Configuration Not Found.

Category:
Installation

Cause:
Entry point not found

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03000
Error: ClassName is blank in roadmap file for page: {0}

Category:
Installation

Cause:
The ClassName provided for the page named {0} is either null or blank or the class is nonexistent.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03001
Error: ClassName is null or not provided in roadmap file for page: {0}

Category:
Installation

Cause:
The ClassName provided for the page named {0} is either null or blank or the class is nonexistent.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03002
Error: Class {0} is not found.

Category:
Installation

Cause:
Either Class {0} is not present or it has an invalid format or it has been compiled with a different version of java compiler.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03003
Internal Error: Runtime error occurred while loading page : {0}

Category:
Installation

Cause:
Error occurred while loading the class for page {0}

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03004
Internal Error: The Resource Key name provided is blank

Category:
Installation

Cause:
Resource Key name provided is blank

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03005
Internal Error: Exception occurred while constructing the Navigation Tree

Category:
Installation

Cause:
Error while constructing the Navigation Tree

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03006
Internal Error: Exception occurred while preparing the Action Queue

Category:
Installation

Cause:
Error occurred while preparing the Action Queue

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03007
Internal Error: Exception occurred while loading the help files.

Category:
Installation

Cause:
The help files are corrupt or the help files are not present.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03008
Internal Error: Exception occurred while parsing the displayConfig.xml file

Category:
Installation

Cause:
The format of displayConfig.xml is corrupt.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03009
Internal Error: Exception occurred launching the welcome window.

Category:
Installation

Cause:
Error occurred launching the welcome window

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03010
Internal Error: Exception occurred launching the Wizard.

Category:
Installation

Cause:
Error occurred launching the Wizard

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03011
Internal Error: Exception occurred while setting the UI default properties.

Category:
Installation

Cause:
Error occurred while setting the UI default properties

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03012
Internal Error: Unknown Exception occurred.

Category:
Installation

Cause:
Unknown exception occurred during installation

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03013
Internal Error: Exception while creating the Wizard Sequence

Category:
Installation

Cause:
The sequence provided in roadmap.xml is not proper.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03014
Internal Error: Exception occurred while creating the validation tree

Category:
Installation

Cause:
Error occurred while creating the validation tree

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03015
Internal Error: Exception occurred while selecting the next page.

Category:
Installation

Cause:
Error occurred while selecting the next page

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03016
Internal Error: Exception occurred while updating the data model with user-specified data

Category:
Installation

Cause:
Error occurred while updating the data model with user-specified data

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03017
Internal Error: Exception occurred while restoring the data from checkpoint.

Category:
Installation

Cause:
The checkpoint data is corrupted.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03018
Internal Error: Exception occurred while shrinking the image.

Category:
Installation

Cause:
Either the image is corrupted or the machine has not enough memory to perform the operation.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03019
Internal Error: Error while fetching the image.

Category:
Installation

Cause:
Either the image is not present or the image is corrupted.

Action:
Provide the following files to Oracle Support Services: \n\n"{0}"\n"{1}"

INST-03020
Error in connecting to the Database. Connect string is missing

Category:
Installation

Cause:
Connect String is missing

Action:
Provide a valid value

INST-03021
Error in connecting to the Database

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-03022
Error in validating Database details. Schema Type is missing

Category:
Installation

Cause:
Schema Type is missing

Action:
Provide a valid value

INST-03023
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Listener could be down

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-03024
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Invalid user name/password

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-03025
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. User is not a SYSDBA

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-03026
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Database could be down

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-03027
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Invalid service id

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-03028
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Invalid service name

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-03029
Error in validating Database details

Category:
Installation

Cause:
Could not find {0} type Schema in the Database

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07000
Error in validating {0} location

Category:
Installation

Cause:
{0} location specified is null or contains invalid characters

Action:
The directory name may only contain alphanumeric, underscore (_), hyphen (-) , or dot (.) characters, and it must begin with an alphanumeric character. Provide a different directory name.

INST-07001
Validation of {0} location failed. Null Value

Category:
Installation

Cause:
Provide a valid value for {0} location.

Action:

INST-07002
Validation of {0} location failed. String is too long.

Category:
Installation

Cause:
Specified {0} location: {1} is too long

Action:
Change the path to a value that is less than or equal to {2} characters

INST-07003
Validation of {0} location failed. Not Absolute.

Category:
Installation

Cause:
{0} location is not absolute path

Action:
Provide an absolute path

INST-07004
Validation of {0} location failed. Invalid Characters.

Category:
Installation

Cause:
{0} location contains one or more invalid characters

Action:
The directory name may only contain alphanumeric, underscore (_), hyphen (-) , or dot (.) characters, and it must begin with an alphanumeric character. Provide a different directory name.

INST-07005
Validation of {0} location failed. Directory already Exists.

Category:
Installation

Cause:
Validation of {0} location failed. The location specified already exists and is a nonempty directory

Action:
Provide an empty or nonexistent directory location

INST-07006
Validation of {0} location failed. No read/write permission.

Category:
Installation

Cause:
Validation of {0} location failed. The location specified does not have read/write permissions

Action:
Provide a location with read/write permission

INST-07007
Validation of {0} location failed. Directory exists as a file.

Category:
Installation

Cause:
Validation of {0} location failed. The location specified already exists and is a file

Action:
Provide an empty or nonexistent directory location

INST-07008
Validation of {0} location failed. No create permission.

Category:
Installation

Cause:
Validation of {0} location failed. User does not have permission to create home/instance location

Action:
Make sure that you have the required permission to create the directory

INST-07009
Error in validating {0} location

Category:
Installation

Cause:
An unexpected error occurred while validating {0} location

Action:
Enter a valid directory

INST-07010
Validation of {0} location failed. String is too long.

Category:
Installation

Cause:
Specified {0} location: {1} is too long

Action:
Change the path to a value that is less than or equal to {3} characters

INST-07011
Validation of Front End URL failed. Null Value

Category:
Installation

Cause:
Provide a valid value for Front End URL

Action:

INST-07012
Validation of Front End URL failed. Invalid Protocol

Category:
Installation

Cause:
Validation of Front End URL failed. The protocol entered is not valid

Action:
Provide a valid protocol. The valid protocol list is {0}

INST-07013
Validation of Hostname failed. Invalid Host

Category:
Installation

Cause:
The hostname entered is not valid

Action:
Provide a valid hostname

INST-07014
Validation of port value failed. Invalid port

Category:
Installation

Cause:
The port entered is not valid

Action:
Provide a valid port number

INST-07015
Validation of Front End URL failed. Invalid format

Category:
Installation

Cause:
Validation of Front End URL failed. The front end URL entered is not valid

Action:
Provide a valid URL in [http://host.domainname:port] format

INST-07016
Error in validating the Front End URL

Category:
Installation

Cause:
An unexpected error occurred while validating the Front End URL

Action:
Provide a valid value

INST-07017
Error in obtaining free space

Category:
Installation

Cause:
Error in obtaining free space. Value for drive name contains invalid characters

Action:
Provide a valid value

INST-07018
Error in obtaining free space. Null Value

Category:
Installation

Cause:
Error in obtaining free space. Value for drive name is null

Action:
Provide a valid value

INST-07019
Error in obtaining free space

Category:
Installation

Cause:
An unexpected error occurred while calculating available free space

Action:
Provide a valid value

INST-07020
Error in obtaining default {0} location

Category:
Installation

Cause:
An unexpected error occurred while obtaining default home location

Action:
Provide a valid value

INST-07021
Error in obtaining available Oracle homes

Category:
Installation

Cause:
An unexpected error occurred while obtaining available Oracle homes

Action:
Provide a valid value

INST-07033
Error in validating the {0} field value

Category:
Installation

Cause:
{0} field value is null or contains invalid characters.

Action:
Provide a valid value

INST-07034
Error in validating the {0} field value

Category:
Installation

Cause:
Provide a value for {0}

Action:

INST-07035
Error in validating the {0} field value. Length less than minimum length

Category:
Installation

Cause:
{0} has less than {1} characters

Action:
Length should be at least {0} characters

INST-07036
Error in validating the {0} field value. Length greater than maximum length

Category:
Installation

Cause:
{0} has more than {1} characters

Action:
Length should not be greater than {0} characters

INST-07037
Error in validating the {0} field value. Invalid characters

Category:
Installation

Cause:
{0} field value contains one or more invalid characters or the value is not in proper format.

Action:
Enter valid characters

INST-07038
Error in validating the {0} field value. Invalid Start character

Category:
Installation

Cause:
{0} field value contains one or more invalid start characters

Action:
Enter valid start character

INST-07039
Error in validating the {0} field value

Category:
Installation

Cause:
An unexpected error occurred while validating {0} field value

Action:
Enter a valid value

INST-07040
Error in Password Check

Category:
Installation

Cause:
Passwords entered were null or contained invalid characters

Action:
Provide valid values

INST-07041
Error in Password Check

Category:
Installation

Cause:
An unexpected error occurred while processing the handler

Action:
Enter passwords that match

INST-07042
Error in Password Check. Password value null

Category:
Installation

Cause:
Password value is null

Action:
Enter a valid value for password

INST-07043
Error in Password Check. Confirm password value null.

Category:
Installation

Cause:
Confirm Password value is null

Action:
Enter a valid value for confirm password

INST-07044
Error in Password Check. Passwords do not match

Category:
Installation

Cause:
Passwords entered do not match

Action:
Enter identical passwords

INST-07045
Error in validating the {0} field value

Category:
Installation

Cause:
An unexpected error occurred while validating {0} field value

Action:
Enter a valid number

INST-07046
Error in validating the {0} field value

Category:
Installation

Cause:
Provide a valid value for {0}

Action:

INST-07047
Error in validating the {0} field value. Not a number

Category:
Installation

Cause:
{0} field value is not a number

Action:
Enter a valid number

INST-07048
Error in Validating {0} and {1}

Category:
Installation

Cause:
Values specified are null or contain invalid characters

Action:
Provide valid values

INST-07049
Error in Validating {0} and {1}

Category:
Installation

Cause:
An unexpected error occurred while validating {0} and {1}

Action:
Enter values that do not match

INST-07050
Error in Validating {0} and {1}. Null Value

Category:
Installation

Cause:
Provide a valid value for {0}

Action:

INST-07051
Error in Validating {0} and {1}. Values do not match

Category:
Installation

Cause:
{0} and {1} are different

Action:
Enter same values

INST-07052
Error in Validating {0} and {1}. Values match

Category:
Installation

Cause:
{0} and {1} are the same

Action:
Enter different values

INST-07053
Error in validating the {0} field value

Category:
Installation

Cause:
{0} field value is null or contains invalid characters

Action:
Provide valid values

INST-07054
Error in validating the {0} field value

Category:
Installation

Cause:
An unexpected error occurred while validating {0} field value

Action:
Enter a valid host name

INST-07055
Error in validating the {0} field value. Host name value null

Category:
Installation

Cause:
Provide a valid value for {0}

Action:

INST-07056
Error in validating the {0} field value. Invalid host name

Category:
Installation

Cause:
{0} field value is not a valid host name

Action:
Enter a valid value for host name

INST-07057
Error in validating the {0} field value. Host is not up and running

Category:
Installation

Cause:
Error in validating the {0} field value. Entered host is not up and running

Action:
Make sure that the host is up and running

INST-07058
Error in validating Oracle home location

Category:
Installation

Cause:
An unexpected error occurred while validating Oracle home location

Action:
Provide a valid value

INST-07059
Error in validating Oracle home location

Category:
Installation

Cause:
Oracle home location Specified is missing. Provide a valid Oracle home location

Action:

INST-07060
Error in validating Oracle home location

Category:
Installation

Cause:
The Oracle home location specified is not a valid {0} home location

Action:
Provide a valid {0} home location

INST-07061
Error in obtaining default port file location

Category:
Installation

Cause:
An unexpected error occurred while obtaining default port file location

Action:
Provide a valid value

INST-07062
Error in connecting to the Database

Category:
Installation

Cause:
An unexpected error occurred while trying to connect to the Database

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07063
Error in connecting to the Database. Connect String is missing

Category:
Installation

Cause:
Connect string is missing

Action:
Provide a valid value for Connection String

INST-07064
Error in connecting to the Database

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07065
Error in validating Database details

Category:
Installation

Cause:
An unexpected error occurred while trying to connect to the Database

Action:
Try again and check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07066
Error in validating Database details. Schema Type is missing

Category:
Installation

Cause:
Schema type is missing

Action:
Provide a valid value for Schema Type

INST-07067
Error in validating Database details. Schema name is missing

Category:
Installation

Cause:
Schema is missing

Action:
Provide a valid value for Schema Name

INST-07068
Error in validating Database details. Invalid Schema

Category:
Installation

Cause:
Specified {0} schema does not exist in the given Database

Action:
Check the schema name and the Database credentials

INST-07069
Validation of {0} location failed. Existing Oracle home

Category:
Installation

Cause:
Validation of {0} location failed. The location specified is an existing Oracle home

Action:
Provide an empty or nonexistent directory location

INST-07072
Error in validating Oracle home location

Category:
Installation

Cause:
The Oracle home location specified is an existing Oracle home

Action:
Provide an empty or nonexistent directory location

INST-07073
Error in validating Oracle home location

Category:
Installation

Cause:
The Oracle home location specified is not a valid {0} home location

Action:
Provide an empty or nonexistent directory location or a valid {0} home location

INST-07074
Error in validating Database details. Null Value

Category:
Installation

Cause:
User name is missing

Action:
Provide a valid user name with DBA privileges

INST-07075
Error in validating Database details. Invalid user

Category:
Installation

Cause:
User does not have DBA privileges

Action:
Provide a user with DBA privileges

INST-07076
Error in validating Database details

Category:
Installation

Cause:
An unexpected error occurred while trying to connect to the Database

Action:
Try again and check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07077
Error in validating Oracle home and Oracle Instance home

Category:
Installation

Cause:
Oracle home is inside the Oracle Instance home

Action:
Enter a different location

INST-07078
Error in validating LDAP credentials

Category:
Installation

Cause:
An unexpected error occurred while validating LDAP credentials

Action:
Provide a valid value

INST-07079
Error in validating LDAP credentials

Category:
Installation

Cause:
Could not connect to LDAP with the given credentials.

Action:
Verify the credentials. Make sure that hostname, port and password are correct

INST-07080
Error in validating available disk space

Category:
Installation

Cause:
Space required is missing or not a valid value

Action:
Provide a valid value

INST-07081
Error in validating available disk space

Category:
Installation

Cause:
Insufficient space to install the selected components

Action:
Specify a different Oracle Home or increase disk space.

INST-07082
Error in validating available disk space

Category:
Installation

Cause:
An unexpected error occurred while validating available disk space

Action:
Provide a valid value

INST-07083
Error in validating port file

Category:
Installation

Cause:
Specified port file location is missing

Action:
Provide a valid value

INST-07084
Error in validating port file

Category:
Installation

Cause:
Specified port file is invalid

Action:
Specify a valid file

INST-07085
Error in validating port file

Category:
Installation

Cause:
Specified port file does not exist

Action:
Specify a valid file

INST-07086
Error in validating port file

Category:
Installation

Cause:
An unexpected error occurred while parsing the port file

Action:
Verify the file. Check if the values are provided in the proper format. There should be at least one section in the file.

INST-07087
Error in validating port file

Category:
Installation

Cause:
An unexpected error occurred while validating port file

Action:
Provide a valid value. Check if the values are provided in the proper format. There should be at least one section in the file.

INST-07088
Error in validating available disk space

Category:
Installation

Cause:
Insufficient disk space to install the product

Action:
Specify a different Oracle Home or increase disk space.

INST-07093
Error in validating port file

Category:
Installation

Cause:
Keys {0} does not have proper values

Action:
Provide valid values. Ensure that the port is free, valid and it is not used by any other Oracle Home

INST-07094
Error in validating port file

Category:
Installation

Cause:
Ports {0} are not free or not valid

Action:
Ensure that the port is free, valid and it is not used by any other Oracle Home. If ports are specified using a file, check if proper values are given for key.

INST-07095
Error in validating port file

Category:
Installation

Cause:
Key {0} does not have proper value

Action:
Provide a valid value

INST-07096
Required component not found in Oracle home

Category:
Installation

Cause:
One or more of the required components required for the install options selected may be missing from the Oracle home

Action:
Specify a valid Oracle home with all required Components

INST-07097
Error in validating component name

Category:
Installation

Cause:
Component name specified is not correct

Action:
Provide a valid component name

INST-07098
Error in validating Oracle home location

Category:
Installation

Cause:
Component {0} is not available in the Oracle home but selected for configuration.

Action:
Deselect the above component for configuration

INST-07099
Error in validating Oracle home location

Category:
Installation

Cause:
Components {0} are not available in the Oracle home but selected for configuration.

Action:
Deselect the above components for configuration

INST-07100
Error in validating port file

Category:
Installation

Cause:
Port {0} is duplicated

Action:
Provide different ports

INST-07101
Error in validating port file

Category:
Installation

Cause:
Ports {0} are duplicated

Action:
Provide different ports

INST-07102
Error in validating port file

Category:
Installation

Cause:
Port {0} is already used by existing Oracle Homes

Action:
Provide a port which is valid and free

INST-07103
Error in validating port file

Category:
Installation

Cause:
Ports {0} are already used by existing Oracle Homes

Action:
Provide port values which are valid and free

INST-07104
Error in validating port file

Category:
Installation

Cause:
Key {0} should not be specified as a range

Action:
Provide a single port which is valid and free

INST-07105
Error in validating port file

Category:
Installation

Cause:
Key {0} should not be specified as a range

Action:
Provide single port values which are valid and free

INST-07106
Error in validating port file

Category:
Installation

Cause:
Port {0} is not free or not valid

Action:
Ensure that the port (a number between 0 - 65535) is free and it is not used by any other Oracle Home. If ports are specified using a file, check if proper values are given for key

INST-07107
Error in validating port value

Category:
Installation

Cause:
An unexpected error occurred while validating port value

Action:
Provide a valid value

INST-07108
Error in validating components selected for configuration

Category:
Installation

Cause:
An unexpected error occurred while processing the handler

Action:
Select valid components

INST-07109
Error in validating components selected for configuration

Category:
Installation

Cause:
At least one component should be selected for configuration

Action:
Select at least one component for configuration

INST-07110
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Invalid service id

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07111
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Invalid service name

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07112
Error in obtaining schema details

Category:
Installation

Cause:
An unexpected error occurred while trying to get schema details

Action:
Try executing again and check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07113
Error in obtaining schema details

Category:
Installation

Cause:
Error in validating schema details. Could not fetch schema details from database

Action:
Try executing again and check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07114
Error in obtaining schema details

Category:
Installation

Cause:
Error in validating schema details. Schema Registry table does not exist

Action:
Provide a Database which has schemas loaded

INST-07115
Error in validating {0} schema details

Category:
Installation

Cause:
An unexpected error occurred while validating {0} schema details

Action:
Try again and check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07119
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Listener could be down

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07120
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Invalid user name/password

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07121
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. User is not a SYSDBA

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07122
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Database could be down

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct. Enter a valid user name with DBA privileges

INST-07123
Error in validating port file

Category:
Installation

Cause:
Specified file is empty or does not contain valid entries

Action:
Provide a valid file

INST-07124
Error in validating Oracle home location

Category:
Installation

Cause:
Component {0} is not available in the Oracle home but selected for installation.

Action:
Deselect the above component

INST-07125
Error in validating Oracle home location

Category:
Installation

Cause:
Components {0} are not available in the Oracle home but selected for installation.

Action:
Deselect the above components

INST-07132
Error in validating jpsRootDN value

Category:
Installation

Cause:
User(s) {0} are not present in the specified LDAP

Action:
Users "fmwadmin" and "systemuser" must be present. The user must also have privileges to create users and groups

INST-07133
Error in obtaining LDAP bindpass

Category:
Installation

Cause:
User {0} does not have permission to create {1}

Action:
Users "fmwadmin" and "systemuser" must be present. The user must also have privileges to create users and groups

INST-07134
Error in validating Oracle Configuration Manager Service credentials

Category:
Installation

Cause:
Customer Identification Number is missing or invalid

Action:
Provide a valid value for Customer Identification Number

INST-07135
Error in validating Oracle Configuration Manager Service credentials

Category:
Installation

Cause:

Action:

INST-07136
Error in validating Oracle Configuration Manager Service credentials

Category:
Installation

Cause:
Country Code value is incorrect

Action:
Provide a valid value for Country Code

INST-07137
Error in validating Oracle Configuration Manager Service credentials

Category:
Installation

Cause:
Could not connect Oracle Configuration Manager Service with the specified credentials

Action:
Verify the values. Make sure the Customer Identification Number, My Oracle Support User Name and the Country code are correct

INST-07138
Error in validating Oracle Configuration Manager Service credentials

Category:
Installation

Cause:
An unexpected error occurred while validating the Oracle Configuration Manager Service credentials

Action:
Verify the values and try again

INST-07139
Error in validating Oracle Configuration Manager Service credentials

Category:
Installation

Cause:
Provide a valid value for Customer Identification Number

Action:
CSI number must contain numeric characters only

INST-07144
Error in validating LDAP Credentials

Category:
Installation

Cause:
Specified LDAP Type ({0}) is not valid

Action:
Valid values are "{0}". Enter a valid LDAP Type

INST-07150
Error in validating jpsRootDN value

Category:
Installation

Cause:
Specified JPS Root DN value is not valid

Action:
Provide a valid value. Make sure that the root DN provided is an empty container.

INST-07151
Error in validating jpsRootDN value

Category:
Installation

Cause:
Provide a valid value for JPS Root DN

Action:

INST-07152
Error in obtaining LDAP Host

Category:
Installation

Cause:
An unexpected error occurred while processing the handler

Action:
Provide a valid value

INST-07153
Error in obtaining LDAP Port

Category:
Installation

Cause:
An unexpected error occurred while processing the handler

Action:
Provide a valid value

INST-07154
Error in obtaining LDAP binddn

Category:
Installation

Cause:
An unexpected error occurred while processing the handler

Action:
Provide a valid value

INST-07155
Error in obtaining LDAP bindpass

Category:
Installation

Cause:
An unexpected error occurred while processing the handler

Action:
Provide a valid value

INST-07156
Error in validating URL

Category:
Installation

Cause:
Provide a valid value the URL

Action:

INST-07157
Error in validating URL

Category:
Installation

Cause:
URL {0} is not valid

Action:
Provide a valid URL in [hostname.domainname:port] format and make sure the given URL is accessible

INST-07158
Error in validating URL

Category:
Installation

Cause:
URL {0} is not accessible.

Action:
Provide a valid URL which is accessible.

INST-07159
Error in validating URL

Category:
Installation

Cause:
An unexpected error occurred while validating the URL

Action:
Verify the values and try again

INST-07169
Error in validating port file

Category:
Installation

Cause:
Port range {0} is not valid. Start range is greater than end range

Action:
Provide a valid port range

INST-07172
Error in validating port file

Category:
Installation

Cause:
Key {0} is missing in the section [{1}]

Action:
Provide a value for the key

INST-07173
Error in validating port file

Category:
Installation

Cause:
Keys {0} are missing in the section [{1}]

Action:
Provide valid value for the keys

INST-07174
Error in validating port file

Category:
Installation

Cause:
Key {0} is not valid in the section [{1}]

Action:
Valid keys for section [{0}] are {1}

INST-07175
Error in validating port file

Category:
Installation

Cause:
Keys {0} were not valid in the section [{1}]

Action:
Valid keys for section [{0}] are {1}

INST-07176
Error in validating port file

Category:
Installation

Cause:
Key {0} is duplicated

Action:
Remove duplicate entries

INST-07177
Error in validating port file

Category:
Installation

Cause:
Keys {0} are duplicated

Action:
Remove duplicate entries

INST-07179
Error in validating port file

Category:
Installation

Cause:
Port range {0} are not valid. Start range is greater than end range

Action:
Provide a valid port range

INST-07180
Error in validating port file

Category:
Installation

Cause:
Specified Port range {0} does not have free port.

Action:
Provide a different range. Check if the same range is mentioned more than once in the file.

INST-07181
Error while obtaining registry key value

Category:
Installation

Cause:
An error occurred while obtaining a registry key value

Action:
Provide a valid value for Registry Key

INST-07182
Error while obtaining registry key value

Category:
Installation

Cause:
An error occurred while obtaining a registry key value

Action:
Provide a valid value for Registry Sub Key

INST-07183
Error while obtaining registry key value

Category:
Installation

Cause:
An error occurred while obtaining a registry key value

Action:
Provide a valid value for Registry Property Name

INST-07184
Error while obtaining registry key value

Category:
Installation

Cause:
An unexpected error occurred while obtaining registry key value

Action:
Verify the values and try again

INST-07185
Error in validating proxy credentials

Category:
Installation

Cause:
Provide a valid value for Proxy Server

Action:

INST-07186
Error in validating proxy credentials

Category:
Installation

Cause:
Provide a valid value for Proxy Port

Action:

INST-07187
Error in validating proxy credentials

Category:
Installation

Cause:
Specified Proxy port is not a valid value

Action:
Provide a valid number for Proxy Port

INST-07188
Error in validating proxy credentials

Category:
Installation

Cause:
Could not establish connection to the specified proxy credentials

Action:
Verify the values. Make sure the proxy server, proxy port values are correct

INST-07189
Error in validating proxy credentials

Category:
Installation

Cause:
An unexpected error occurred while obtaining registry key value

Action:
Verify the values and try again

INST-07202
Error in validating container name

Category:
Installation

Cause:
Provide a valid value for container name

Action:

INST-07203
Error in validating container name

Category:
Installation

Cause:
Specified value is a reserved key word.

Action:
Provide value other than {0}

INST-07204
Error in validating container name

Category:
Installation

Cause:
An unexpected error occurred while validating the URL

Action:
Verify the values and try again

INST-07205
Error in validating port file

Category:
Installation

Cause:
Port {0} is duplicated for keys {1}

Action:
Provide different ports

INST-07206
Error in validating port file

Category:
Installation

Cause:
Port {0} (JMX Port No + 1) is not free

Action:
JMX Port No + 1 will be used as Java Object Cache Local Port No. Specify a value for Java Object Cache Local Port No key or provide a JMX Port No which has also (JMX Port No + 1) free

INST-07207
Error in validating port file

Category:
Installation

Cause:
Port {0} (JMX Port No + 2) is not free

Action:
JMX Port No + 2 will be used as Java Object Cache Remote Port No. Specify a value for Java Object Cache Remote Port No key or provide a JMX Port No which has also (JMX Port No + 2) free

INST-07208
Error in validating port file

Category:
Installation

Cause:
Reserved ports are not allowed under section [{0}]. Key(s) {1} have Operating System reserved port entries.

Action:
Provide different port(s)

INST-07210
Error in obtaining 10g SSO information

Category:
Installation

Cause:
An unexpected error occurred while obtaining 10g SSO information

Action:
Verify the LDAP credentials. Make sure that hostname, port, binddn, password are correct

INST-07211
Error in obtaining Oracle Internet Directory version

Category:
Installation

Cause:
An unexpected error occurred while processing the handler

Action:
Provide a valid value

INST-07212
Error in checking the version of Oracle Internet Directory

Category:
Installation

Cause:
Version of the given Oracle Internet Directory is not {0}

Action:
Provide an alternate Oracle Internet Directory location

INST-07213
Error in checking the version of Oracle Internet Directory

Category:
Installation

Cause:
An unexpected error occurred while checking the version of Oracle Internet Directory

Action:
Verify the LDAP credentials. Make sure that hostname, port, binddn, password are correct

INST-07214
Error in validating URL

Category:
Installation

Cause:
Specified URL is not valid

Action:
Provide a valid value for the URL

INST-07215
Error in validating URL

Category:
Installation

Cause:
Specified URL is not correct format

Action:
Provide a valid URL

INST-07216
Error in validating URL

Category:
Installation

Cause:
Specified URL is not accessible

Action:
Provide a valid URL

INST-07217
Error in validating URL

Category:
Installation

Cause:
Specified URL is not accessible

Action:
Provide a valid URL

INST-07221
Error in validating database details

Category:
Installation

Cause:
Specified connect string is not in a valid format

Action:
Provide the value in the following format. Format: hostname:port:servicename , For Real Application Cluster Database hostname1:port1^hostname2:port2@servicename

INST-07222
Error in validating database details

Category:
Installation

Cause:
Specified connect string is not in a valid format

Action:
Provide the value in the following format. Format: hostname:port:sid , For a Real Application Cluster Database, use hostname1:port1^hostname2:port2@servicename

INST-07223
Error in obtaining work repository details

Category:
Installation

Cause:
Work repository table does not exist

Action:
Provide a Database which has repositories loaded

INST-07224
Error in obtaining work repository details

Category:
Installation

Cause:
Error in obtaining work repository details. Could not fetch repository details from database

Action:
Try executing again and check the values. Make sure the Database is up and running and connect string, user name and password are correct.

INST-07225
Error in validating work repository details

Category:
Installation

Cause:
An unexpected error occurred while validating work repository details

Action:
Try again and check the values. Make sure the Database is up and running and connect string, user name and password are correct.

INST-07226
Error in validating Database details. Invalid Work Repository

Category:
Installation

Cause:
Specified {0} repository does not exist in the given Database

Action:
Check the {0} repository name and the Database credentials

INST-07227
Error in validating work repository details

Category:
Installation

Cause:
Provide a valid {0} repository name

Action:

INST-07228
Error in connecting to the Database

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct.

INST-07229
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Listener could be down

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct

INST-07230
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Invalid user name/password

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct

INST-07231
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. User is not a SYSDBA

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct

INST-07232
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Database could be down

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct

INST-07233
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Invalid service id

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct

INST-07234
Error in validating Database details

Category:
Installation

Cause:
Unable to connect to the Database with the given credentials. Invalid service name

Action:
Check the values. Make sure the Database is up and running and connect string, user name and password are correct

INST-07235
Error in validating the {0} field value

Category:
Installation

Cause:
Please enter the {0} field value in the range {1} - {2}

Action:

INST-07236
Error in validating the agent name

Category:
Installation

Cause:
Provide a valid value for the agent name

Action:

INST-07237
Error in validating the agent name

Category:
Installation

Cause:
Agent name already exists. Provide a different value

Action:

INST-07238
Error in validating the agent name

Category:
Installation

Cause:
Unable to verify the agent name

Action:
Verify the values. Make sure the Master Database is up and running and connect string, user name, password, ODI supervisor username and ODI supervisor password are correct.

INST-07239
Database details are invalid.

Category:
Installation

Cause:
The specified schema {0} was invalid.

Action:
Check the schema name and database credentials.

INST-07240
{0} components cannot be obtained from the Oracle WebLogic Middleware Administration Server.

Category:
Installation

Cause:
The Oracle WebLogic Middleware Administration Server may be unresponsive or may not recognize the given credentials.

Action:
Make sure the Oracle WebLogic Middleware Administration Server is up. Verify that the host name, port number, user name, and administrator password are correct.

INST-07241
Connection to the Oracle WebLogic Middleware Administration Server has failed.

Category:
Installation

Cause:
The provided credentials were null or contained invalid characters.

Action:
Make sure the Middleware Administration Server is up and hostname, port, user name and administration password are correct.

INST-07242
Connection to the Oracle WebLogic Middleware Administration Server has failed.

Category:
Installation

Cause:
The Oracle Middleware Administration Server may be down. The provided credentials may be incorrect.

Action:
Make sure the Oracle Middleware Administration Server is up and running. Verify that the host name, port number, user name, and administrator password are all correct.

INST-07243
Connection to the Oracle WebLogic Middleware Administration Server has failed.

Category:
Installation

Cause:
Host name was missing.

Action:
Enter a valid host name.

INST-07244
Connection to the Oracle WebLogic Middleware Administration Server has failed.

Category:
Installation

Cause:
The port number was missing.

Action:
Enter a valid port number.

INST-07245
Connection to the Oracle WebLogic Middleware Administration Server has failed.

Category:
Installation

Cause:
The administrator user name is missing.

Action:
Enter a valid administrator user name.

INST-07246
{0} home location cannot be validated.

Category:
Installation

Cause:
The home location is invalid.

Action:
Enter a valid value for {0} home location.

INST-07247
{0} home location cannot be validated.

Category:
Installation

Cause:
Specified {0} home location is either not valid or missing.

Action:
Enter a valid {0} home location.

INST-07248
{0} home location cannot be validated.

Category:
Installation

Cause:
Specified {0} home location was not valid.

Action:
Enter a valid {0} home location.

INST-07249
{0} home location cannot be validated.

Category:
Installation

Cause:
An unexpected error occurred during the validation of {0} home location.

Action:
Check the values.

INST-07250
Error in validating Middleware home and WebLogic home

Category:
Installation

Cause:
Specified WebLogic home is not associated with the given Middleware home

Action:
Enter a WebLogic home that is associated with the specified Oracle Middleware home

INST-07251
Error in validating Middleware home and WebLogic home

Category:
Installation

Cause:
An unexpected error occurred during the validation of Oracle Middleware home and WebLogic home

Action:
Check the values

INST-07252
Default Middleware home and WebLogic home directories cannot be obtained.

Category:
Installation

Cause:
An unexpected error occurred while obtaining default Oracle Middleware home and WebLogic home directories.

Action:
Check the values.

INST-07253
Instance name cannot be validated.

Category:
Installation

Cause:
Specified instance name is not valid.

Action:
Enter a valid instance name associated with the specified instance home.

INST-07254
Instance name cannot be validated.

Category:
Installation

Cause:
An unexpected error occurred.

Action:
Check the inputted values.

INST-07255
Instance name cannot be validated.

Category:
Installation

Cause:
The specified instance name was incorrect.

Action:
Enter a valid instance name.

INST-07256
{0} component name cannot be validated.

Category:
Installation

Cause:
Component type failed validation.

Action:
Enter a valid value for {0} component name.

INST-07257
Component type cannot be validated.

Category:
Installation

Cause:
The specified component type failed validation.

Action:
Enter a valid value for component type.

INST-07258
Component name cannot be validated.

Category:
Installation

Cause:
The provided component name could not be located.

Action:
Verify the instance home location. Ensure that the component name is correct.

INST-07259
{0} component name cannot be validated.

Category:
Installation

Cause:
The specified value for {0} component name already exists.

Action:
Provide a different value.

INST-07260
Error in validating {0} component name

Category:
Installation

Cause:
Specified value for {0} component name is not valid. A directory with the same name already exists under INST_HOME/config/{0}

Action:
Provide a different value

INST-07261
Error in validating component name

Category:
Installation

Cause:
Specified component name is not a valid component name

Action:
Enter a valid component name associated with the specified instance

INST-07262
Error in validating instance details in the domain

Category:
Installation

Cause:
Specified instance details are not valid

Action:
Enter a valid instance name available in the domain. Make sure the instance home entered is in conjunction with the instance name.

INST-07263
Error in validating instance name

Category:
Installation

Cause:
Specified instance name is not valid

Action:
Enter a valid instance name available in the domain.

INST-07264
Error in validating instance details in the domain

Category:
Installation

Cause:
An unexpected error occurred during the validation of instance details

Action:
Check the values. Verify the instance name and instance home location

INST-07265
Error in validating instance name

Category:
Installation

Cause:
An unexpected error occurred during the validation of instance name

Action:
Check the values. Verify the instance name

INST-07266
Error in validating component name in the domain

Category:
Installation

Cause:
Specified {0} component name already exists in the domain

Action:
Provide a different value

INST-07267
Error in validating component name in the domain

Category:
Installation

Cause:
An unexpected error occurred during the validation of component name

Action:
Check the values. Verify the component name

INST-07268
Error in validating component name in the domain

Category:
Installation

Cause:
Specified {0} component name does not exist in the domain

Action:
Enter an existing component name

INST-07269
Error while obtaining default values for instance name and instance location

Category:
Installation

Cause:
An unexpected error occurred while obtaining default values for instance name and instance location

Action:
Check the values and try again

INST-07270
Error in validating instance name in the domain

Category:
Installation

Cause:
Specified instance name already exists in the domain

Action:
Provide a different value

INST-07271
Error in validating instance name in the domain

Category:
Installation

Cause:
An unexpected error occurred during the validation of instance name

Action:
Check the values. Verify the instance name

INST-07272
Error while obtaining the component names from the instance home

Category:
Installation

Cause:
An unexpected error occurred while obtaining the component names from the instance home

Action:
Check the values. Verify the instance home location

INST-07273
Error while obtaining the component names of a given component type from the instance home

Category:
Installation

Cause:
An unexpected error occurred while obtaining the component names of a given component type from the instance home

Action:
Check the values. Verify the instance home location

INST-07274
Error in validating port value

Category:
Installation

Cause:
Port {0} is not valid. Privileged ports are not allowed

Action:
Provide a different value

INST-07275
Error in validating {0} home location

Category:
Installation

Cause:
Specified {0} home location does not have read/write permissions

Action:
Provide read/write permissions for the {0} home location

INST-07276
Error in validating {0} home location

Category:
Installation

Cause:
Enter a valid value for {0} home location

Action:

INST-07277
Error in validating {0} name

Category:
Installation

Cause:
Specified {0} name is either not valid or the corresponding location is not empty

Action:
Enter a valid {0} name

INST-07278
Error in validating {0} home location

Category:
Installation

Cause:
Specified {0} home location does not have Read/Write permissions

Action:
Provide Read/Write permissions for the specified {0} home location

INST-07279
Error in validating {0} home location

Category:
Installation

Cause:
An unexpected error occurred during the validation of {0} home location

Action:
Check the values

INST-07280
Error in validating domain credentials

Category:
Installation

Cause:

Action:

INST-07281
Error in validating domain credentials

Category:
Installation

Cause:
{0} is not set up in the specified domain

Action:
Enter a domain which has {0} set up

INST-07282
Error in validating {0} home location

Category:
Installation

Cause:
Specified {0} home location does not exist

Action:
Provide an existing {0} home location

INST-07285
Error in validating Database details. Invalid Schema

Category:
Installation

Cause:
The schema name {0} and schema type {1} do not match

Action:
Provide a valid schema name for {1}

INST-07286
Error in validating Middleware home location

Category:
Installation

Cause:
Specified Oracle Middleware home location does not have minimum version {0} of WebLogic server. If the version is incorrect then configuring with the Weblogic server will fail.

Action:
Provide a Oracle Middleware home location which contains WebLogic server with minimum version {0} or upgrade the Weblogic server to {0} or higher version and restart the install.

INST-07287
Error in obtaining connection with Oracle WebLogic Middleware Administration Server

Category:
Installation

Cause:
Unable to connect to Oracle WebLogic Middleware Administration Server. Server is not running.

Action:
Make sure the Middleware Administration Server is up

INST-07288
Error in obtaining connection with Oracle WebLogic Middleware Administration Server

Category:
Installation

Cause:
Unable to connect to Oracle WebLogic Middleware Administration Server. Invalid username/ password

Action:
Enter a valid username and password

INST-07289
Error in validating WebLogic Server Directory

Category:
Installation

Cause:
Specified WebLogic Server Directory is either not valid or empty

Action:
Enter a valid WebLogic Server Directory

INST-07290
Error in validating Oracle home location

Category:
Installation

Cause:
Specified Middleware home already has a {0} home. Only one {0} home location can reside under a Middleware home.

Action:
Provide a different Middleware home location

INST-07291
Error in validating Oracle home location

Category:
Installation

Cause:
Top Component name specified is null.

Action:
Provide a valid component name

INST-07292
Error in validating Middleware home location

Category:
Installation

Cause:
Middleware home location specified is not a valid location. Provide a valid Middleware home location

Action:
Provide a valid Middleware home location.

INST-07293
Error in validating SSO credentials

Category:
Installation

Cause:
Given OID does not have a proper SSO.

Action:
Provide an OID with a 10g SSO.

INST-07294
Error in validating SSO credentials

Category:
Installation

Cause:
Could not retrieve SSO information with the given credentials.

Action:
Verify the credentials. Make sure that hostname, port and password are correct

INST-07295
Error in validating UCM Installer Location

Category:
Installation

Cause:
Specified UCM Installer Location is not valid

Action:
Provide a valid value for UCM Installer Location.

INST-07296
Error in validating UCM Installer Location

Category:
Installation

Cause:
An unexpected error occurred while processing the handler

Action:
Provide a valid value

INST-07297
Error in validating Web Server HTTP Address

Category:
Installation

Cause:
Webserver HTTP Address is missing

Action:
Provide a valid value for Webserver HTTP Address

INST-07298
Error in validating Web Server HTTP Address

Category:
Installation

Cause:
Specified Web Server HTTP Address is not valid

Action:
The Web Server HTTP Address has to be in http(s)://[host]:[port]?/[webroot] format

INST-07299
Error in validating Web Server HTTP Address

Category:
Installation

Cause:
An unexpected error occurred while processing the handler

Action:
Provide a valid value

INST-07300
Error in validating UCM Installer Location

Category:
Installation

Cause:
UCM Installer Location is missing

Action:
Provide a valid value for UCM Installer Location

INST-07301
Error in validating UCM Installer Location

Category:
Installation

Cause:
Specified UCM Installer Location is empty

Action:
Provide a valid value for UCM Installer Location.

INST-07302
Error in validating Domain

Category:
Installation

Cause:
Specified domain cannot be used for Expand Cluster configuration

Action:
Specify a domain which has clusters

INST-07303
Error in validating Domain

Category:
Installation

Cause:
Specified domain cannot be used for Extend Domain configuration

Action:
Specify a domain which has at least one component not configured

INST-07304
Validation of User Name failed. Invalid User Name

Category:
Installation

Cause:
The user name entered is not valid

Action:
Provide a valid user name

INST-07305
Validation of password value failed. Invalid password

Category:
Installation

Cause:
The password entered is not valid

Action:
Provide a valid password

INST-07306
Error in validating Database details. RAC Dabase is not supported

Category:
Installation

Cause:
RAC Database is not supported for {0}

Action:
{0}

INST-07307
Error in validating Oracle home location

Category:
Installation

Cause:
Oracle home location specified is not inside Middleware home location. Provide a valid location for Oracle home.

Action:

INST-07308
Oracle Universal Content Management is already installed and configured at location {0}

Category:
Installation

Cause:
Oracle Universal Content Management is already installed and configured at location {0}

Action:
Either select not to configure again or uninstall Oracle Universal Content Management and then try to reconfigure

INST-07309
Error in validating master repository details

Category:
Installation

Cause:
Specified Master Repository credentials are not valid.

Action:
Verify the values. Make sure the Master Database is up and running and connect string, user name, password, ODI supervisor username and ODI supervisor password are correct.

INST-07310
Error in validating database details

Category:
Installation

Cause:
Specified connect string is not in a valid format

Action:
Provide the value in the following format. Format: hostname:port:servicename

INST-07311
Error in validating database details

Category:
Installation

Cause:
Specified connect string is not in a valid format

Action:
Provide the value in the following format. Format: hostname:port:sid

INST-07312
Error in validating database details

Category:
Installation

Cause:
Specified connect string is not in a valid format

Action:
Provide the value in the following format. Format: hostname:port:servicename , For Real Application Cluster Database hostname1:port1^hostname2:port2@servicename

INST-07313
Error in validating database details

Category:
Installation

Cause:
Specified connect string is not in a valid format

Action:
Provide the value in the following format. Format: hostname:port:sid , For a Real Application Cluster Database, use hostname1:port1^hostname2:port2@servicename

INST-07314
Error in validating port file

Category:
Installation

Cause:
Port {0} is not valid

Action:
Provide a valid port number (a number between {0})

INST-07315
Error in validating port value

Category:
Installation

Cause:
An unexpected error occurred while validating port value

Action:
Provide a valid value

INST-07316
Error in validating port file

Category:
Installation

Cause:
Port {0} is not free or not valid

Action:
Ensure that the port (a number between 1024 - 65535) is free and it is not used by any other Oracle Home. If ports are specified using a file, check if proper values are given for key.

INST-07317
Validation of {0} location failed. Directory does not exist.

Category:
Installation

Cause:
Validation of {0} location failed. The location specified does not exist.

Action:
Enter a valid existing directory

INST-07318
Validation of {0} location failed. Directory s empty.

Category:
Installation

Cause:
Validation of {0} location failed. The location specified is empty.

Action:
Enter a nonempty directory

INST-07319
Validation of {0} location failed. Directory already exists and is not a valid Oracle Home directory.

Category:
Installation

Cause:
Validation of {0} location failed. The location specified already exists and is a nonempty directory and not a valid Oracle Home

Action:
Provide an empty or nonexistent directory location, or a valid existing Oracle Home

INST-07320
Validation of {0} location failed. String is too long.

Category:
Installation

Cause:
Specified {0} location: {1} is too long

Action:
Change the path to a value that is less than or equal to 256 characters

INST-07404
Error in validating Oracle home

Category:
Installation

Cause:
Specified Oracle home value is null

Action:
Specify the correct Oracle home name

INST-07405
Error in validating Oracle home

Category:
Installation

Cause:
The specified Oracle home does not match with the Domain Oracle home

Action:
Specify Oracle home name same as that of the Domain Oracle home

INST-07406
Error in validating {0} home location

Category:
Installation

Cause:
Specified {0} home location is either not valid or is empty

Action:
Enter a valid {0} home location

INST-07407
Error in detecting machine platform or JVM bits.

Category:
Installation

Cause:
Unable to detect machine platform or JVM bits.

Action:
Make sure machine platform and JVM are supported.

INST-07408
Cannot install or configure the product on a 32-bit JVM on a 64-bit machine.

Category:
Installation

Cause:
Unable to install or configure the product on a 32-bit JVM on a 64-bit machine.

Action:
Make sure to install and configure the product in supported modes.

INST-07409
Error in validating instance name

Category:
Installation

Cause:
Unexpected error in validating instance name

Action:
Make sure entered values are correct

INST-07410
Error in validating instance name

Category:
Installation

Cause:
Specified instance name is not valid, a windows service with the specified instance name already exists

Action:
Provide a different instance name

INST-07411
Error in validating oracle home

Category:
Installation

Cause:
Provide valid value for Oracle Home Directory.

Action:

INST-07412
Error in validating Oracle Home

Category:
Installation

Cause:
Oracle Home Directory name cannot be oracle_common.

Action:
Provide a different value for Oracle Home Directory.

INST-07413
Error in validating Oracle Home

Category:
Installation

Cause:
Unexpected error in validating Oracle Home Directory

Action:
Make sure entered values are correct

INST-07414
Error in validating {0}

Category:
Installation

Cause:
Specified {0} is not valid

Action:
Provide a valid value {0}

INST-07415
Error in validating Home Type

Category:
Installation

Cause:
Home Type Specified is not Correct

Action:
Provide a valid a valid Home Type

INST-07416
Error in validating {0}

Category:
Installation

Cause:
An unexpected error occurred while validating {0}

Action:
Provide a valid value

INST-07417
Error in validating the {0}

Category:
Installation

Cause:
{0} has not been installed in the specified {1}. Provide a different Location

Action:
Provide a different {0}

INST-07420
Error in validating Oracle Home

Category:
Installation

Cause:
Oracle Home Directory name cannot be {0}.

Action:
Provide a different value for Oracle Home Directory.

INST-07421
Error in executing the software update flow

Category:
Installation

Cause:
An error occurred while validating the values for software updates

Action:
Make sure entered values are correct

INST-07422
Error in validating library

Category:
Installation

Cause:
The library {0} does not exists in the provided location

Action:
Make sure the library {0} exists in the provided location

INST-07423
Error in validating library

Category:
Installation

Cause:
The library {0} does not exists in the provided location

Action:
Make sure the library {0} exists in the provided location

INST-07424
Error in validating library

Category:
Installation

Cause:
The version of library at the provided location is not as expected

Action:
Make sure the version of library at the provided location is correct

INST-07425
Error in verifying version of Application Server

Category:
Installation

Cause:
Could not access versionInfo script under the Application Server Directory provided

Action:
Make sure the the Application Server directory has versionInfo script under bin folder

INST-07426
Error in verifying version of Application Server

Category:
Installation

Cause:
The version of Application Server is not valid

Action:
Make sure the the version of Application Server is at least {0}

INST-07427
Error in verifying Application Server

Category:
Installation

Cause:
The Application Server Directory does not refer to WebSphere Application Server

Action:
Provide the directory location of WebSphere Application Server

INST-07440
Error in validating Application Server Type

Category:
Installation

Cause:
Validation of Application Server Type failed. Supported Application Server Types are WLS and WAS.

Action:
Specify a valid Application Server Type. Supported Application Server Types are WLS and WAS.

INST-07441
Error in validating Application Server Type

Category:
Installation

Cause:
Validation of Application Server Type failed. Specified Application Server Type does not match with the Application Server detected in the Middleware home.

Action:
Specify a valid Application Server Type.

INST-07509
Error in validating master repository details

Category:
Installation

Cause:
Specified Master Repository schema details are not valid.

Action:
Verify the values. Make sure the Master Database schema version is correct and master repository is created with appropriate Repository Creation Utility.

INST-07520
Error in validating {0} location

Category:
Installation

Cause:
Enter a valid value for {0} location

Action:

INST-07521
Error in validating {0} home location

Category:
Installation

Cause:
Specified {0} home location does not exist

Action:
Provide an exisiting {0} home location

INST-07522
Error in validating {0} home location

Category:
Installation

Cause:
Specified {0} home location does not have read/write permissions

Action:
Provide read/write permissions for the {0} home location

INST-07523
Error in validating {0} home location

Category:
Installation

Cause:
Specified {0} home location is either not valid or empty

Action:
Enter a valid {0} home location

INST-07524
Error in validating {0} home location

Category:
Installation

Cause:
Specified {0} home location is not a valid location

Action:
Enter a valid {0} home location

INST-07525
Error in validating {0} home location

Category:
Installation

Cause:
An unexpected error occurred during the validation of {0} home location

Action:
Check the values

INST-07526
Error in validating {0} home location

Category:
Installation

Cause:
Specified {0} home location is not a valid location

Action:
Enter a valid {0} home location

INST-07527
Error in validating Middleware home location

Category:
Installation

Cause:
Specified Oracle Middleware home location does not have appropriate version of WebLogic server

Action:
Provide a Oracle Middleware home location which contains WebLogic server with a supported version

INST-07528
Validation of {0} location failed. Directory does not exist.

Category:
Installation

Cause:
Validation of {0} location failed. The location specified does not exist.

Action:
Enter a valid existing directory

INST-07529
Error in validating Farm Name

Category:
Installation

Cause:
Farm Name cannot be {0}.

Action:
Enter a different Farm Name.

INST-07530
Patchset component found in Oracle home

Category:
Installation

Cause:
This Patchset has already been applied to the Oracle home

Action:
Specify an Oracle home where the patchset has not already been applied.

INST-07531
Error in validating contents of Oracle home

Category:
Installation

Cause:
The Oracle home provided does not contain {0}.

Action:
In order to patch your existing version please provide an Oracle home that contains the product mentioned above. If you choose to continue, only the oracle_common directory and any components that both products have in common will be patched.

INST-07532
Error in validating contents of Oracle home

Category:
Installation

Cause:
The Oracle home provided does not contain {0}.

Action:
In order to patch your existing version please provide an Oracle home that contains the product mentioned above. If you choose to continue, only the oracle_common directory and any components that both products have in common will be patched.

INST-07533
Error in validating Middleware home location

Category:
Installation

Cause:
Middleware home location specified is missing.

Action:
Provide a valid Middleware home location

INST-07534
Error in validating Oracle home location

Category:
Installation

Cause:
Oracle home location specified is not inside Middleware home location. Provide a directory name only for Oracle home.

Action:
Provide a different Oracle home location which is inside Middleware home.

INST-07535
Error in obtaining hostname

Category:
Installation

Cause:
An unexpected error occurred while retrieving hostname

Action:
Provide a valid value

INST-07536
Error in validating Oracle home location

Category:
Installation

Cause:
Middleware home location specified does not have the required Oracle homes installed in it. The Oracle homes for the following components are not installed: {0}.

Action:
Provide a different Middleware home location or install the required Oracle Products and try the install again

INST-07537
The weblogic server processes are still running.

Category:
Installation

Cause:
Unable to install while the weblogic processes are running.

Action:
Make sure that the node manager and the weblogic servers are shutdown before the installation.

INST-07538
The OPMN processes are still running.

Category:
Installation

Cause:
Unable to install while the OPMN processes are running.

Action:
Make sure that opmnctl stopall is run before the installation.

INST-07539
{0} found in Oracle home

Category:
Installation

Cause:
This Oracle home already contains a version of {0} which cannot be updated by this installation

Action:
Specify either a new Oracle Home Directory or an Oracle Home which can be updated by this installer.

INST-07540
Missing Dependent Feature sets in {0}

Category:
Installation

Cause:
Enter a valid {0} which has all required dependent featuresets

Action:

INST-07541
Error in validating Feature set Dependencies in {0}

Category:
Installation

Cause:
Unexpected Error

Action:

INST-07542
Error in validating Oracle Home location.

Category:
Installation

Cause:
The distribution {0} is not installed in the given Oracle Home.

Action:
Choose a different Oracle Home location.

INST-07543
Error in validating Oracle Home location.

Category:
Installation

Cause:
{0} cannot be installed in an Oracle Home that has {1} already installed.

Action:
Choose a different Oracle Home location.

INST-07544
Error in validating Oracle Home location.

Category:
Installation

Cause:
Oracle Home provided is null or empty

Action:
Provide a different Oracle Home location.

INST-07545
Error in validation. Unexpected Error

Category:
Installation

Cause:
Unexpected Error. {0}

Action:

INST-07546
Error in validating installation type.

Category:
Installation

Cause:
Unable to find install type {0}

Action:
Provide a valid install type

INST-07547
Incompatible installation type.

Category:
Installation

Cause:
Incompatible installation type provided. {0}

Action:
Select a valid install type. Check http://www.oracle.com/pls/topic/lookup?ctx=fmw122130&id=installhome for details about compatible products and install types.

INST-07548
No compatible installation type found.

Category:
Installation

Cause:
The selected distribution does not have any compatible install type for the selected Oracle Home.

Action:
Provide a different oracle Home. Check http://www.oracle.com/pls/topic/lookup?ctx=fmw122130&id=installhome for details about compatible products and install types.

INST-07549
No compatible installation type found.

Category:
Installation

Cause:
Incompatible Installation Type : {0}

Action:
Incompatibility Details : {0}

INST-07550
Unable to find dependent featuresets for the selected installation type

Category:
Installation

Cause:
Unable to find dependent featuresets for the selected installation type. {0}

Action:
Select a different install type or provide a different Oracle Home having all dependencies. Check http://www.oracle.com/pls/topic/lookup?ctx=fmw122130&id=installhome for details about compatible products and install types.

INST-07551
Unable to find dependent featuresets for the selected installation type

Category:
Installation

Cause:
Not all dependent featuresets for install type "{0}" could be found. {1}

Action:
Select a different Oracle Home having all dependencies. Check http://www.oracle.com/pls/topic/lookup?ctx=fmw122130&id=installhome for details about compatible products and install types.

INST-07939
Error in validating install types

Category:
Installation

Cause:
Unexpected error in validating install types

Action:
Make sure entered values are correct

INST-07940
Error in validating install types

Category:
Installation

Cause:
This installation type cannot be installed, because the selected Oracle Home contains Oracle Fusion Middleware Infrastructure.

Action:
For more information about the prerequisites for this install type, see Installing and Configuring Oracle HTTP Server in the Oracle Fusion Middleware documentation library.

INST-07941
Error in validating install types

Category:
Installation

Cause:
This installation type cannot be installed, because Oracle Fusion Middleware Infrastructure is not installed in the selected Oracle Home.

Action:
For more information about the prerequisites for this install type, see Installing and Configuring Oracle HTTP Server in the Oracle Fusion Middleware documentation library.

INST-08001
Validation of Middleware home location failed. Directory path invalid

Category:
Installation

Cause:
Validation of Middleware home location failed. The location specified contains missing, mandatory directories

Action:
Make sure that Oracle/Middleware is in the path

INST-10001
Error in validating Component Dependency Details

Category:
Installation

Cause:
Dependency for {0} is missing. Missing dependent component ids are {1}.

Action:
Make sure to select / specify all dependent components

INST-10002
Error in validating Component Dependency Details

Category:
Installation

Cause:
Component Ids {0} are invalid

Action:
Provide valid component id

INST-10003
Error in validating Component Dependency Details

Category:
Installation

Cause:
An unexpected error occurred while validating Component Dependency Details

Action:
Check the values

INST-10101
Error in validating {0} Base Image Location

Category:
Installation

Cause:
{0} Base Image Location is null or blank.

Action:
Provide a valid {0} Base Image Location

INST-10102
Error in validating {0} Base Image Location

Category:
Installation

Cause:
The {0} Base Image Location provided is not existing or not a valid file

Action:
Provide a valid {0} Base Image Location

INST-10103
Error in validating the {0} Base Image Location for Assembly Builder

Category:
Installation

Cause:
An unexpected error occurred while validating the {0} Base Image Location for Assembly Builder

Action:
Check the values

INST-10104
Error in validating {0} Base Image Location

Category:
Installation

Cause:
The {0} Base Image File name must be {1}

Action:
Provide a valid {0} Base Image Location

INST-10105
Error in validating {0} Base Image Virtual Machine configuration file Location

Category:
Installation

Cause:
The {0} Base Image Virtual Machine configuration File (vm.cfg) is not existing

Action:
The vm.cfg file must be present in same directory as the Base Image ({1}), provide a valid {0} Base Image Location

INST-10106
Error in validating Keystore

Category:
Installation

Cause:
An unexpected error occurred while validating the {0} Keystore for Assembly Builder

Action:
Check the values

INST-10107
The Keystore path must not be null or blank

Category:
Installation

Cause:
The Keystore path must not be null or blank

Action:
Provide a valid Keystore path

INST-10108
The Keystore password must not be null or blank

Category:
Installation

Cause:
The Keystore password must not be null or blank

Action:
Provide a valid Keystore password

INST-10109
Invalid keystore.

Category:
Installation

Cause:
Failed to validate the Keystore.

Action:
Provide a valid Keystore

INST-10110
The Key password must not be null or blank

Category:
Installation

Cause:
The Key password must not be null or blank

Action:
Provide a valid Key password

INST-10111
The Key alias must not be null or blank

Category:
Installation

Cause:
The Key alias must not be null or blank

Action:
Provide a valid Key alias

INST-10112
Invalid key alias

Category:
Installation

Cause:
Invalid key alias and password combination.

Action:
Provide a valid Key alias and password combination

INST-10113
Error in validating Component Version

Category:
Installation

Cause:
Component Version is null or blank.

Action:
Provide a valid Component Version.

INST-10114
Error in validating Component List

Category:
Installation

Cause:
Component List is null or blank.

Action:
Provide a valid Component List.

INST-10115
Error in validating Oracle Home

Category:
Installation

Cause:
Oracle Home is null or blank.

Action:
Provide a valid Oracle Home.

INST-10116
Installation of Studio and Deployer detected in the selected Oracle Home. Installing into an existing Oracle Home is done to either reinstall binaries or to upgrade an Oracle Home from one release to another

Category:
Installation

Cause:
Installation of Studio and Deployer detected in the selected Oracle Home.

Action:
Installing into an existing Oracle Home is done to either reinstall binaries or to upgrade an Oracle Home from one release to another.

INST-10117
Error in validating the installed component in {0} Oracle Home

Category:
Installation

Cause:
An unexpected error occurred while validating the installed component in {0} Oracle Home

Action:
An unexpected error occurred while validating the installed component in {0} Oracle Home

16
J2EE HTTPC-00004 to J2EE HTTPC-12011

J2EE HTTPC-00004
Unable to parse header value: name={0}, value="{1}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-00015
Unable to read response for method={0}, path+query="{1}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-00016
Unable to read response for input stream hashcode={0}.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-00017
Socks: V4 request failure: {0}

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01000
Unable to register built-in AuthenticationScheme {0}.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01001
Unable to register AuthenticationScheme {0} for scheme name {1}.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01002
Unable to add NTLM credentials. The AuthorizationHandler does not implement the AuthenticationSchemeRegistryHolder interface.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01004
Unable to add NTLM credentials. NTLM AuthenticationScheme was not found in the AuthorizationHandler"s AuthenticationSchemeRegistry.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01010
AuthM: Handling deferred authorization challenge.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01011
AuthM: Sending request with Authorization = "{0}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01012
AuthM: Sending request with Proxy-Authorization = "{0}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01013
AuthM: Preemptively sending Proxy-Authorization "{0}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01014
AuthM: Preemptively sending Authorization "{0}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01015
AuthM: Server refused the given Authorization info {0} times, aborting request.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01016
AuthM: Status {0} not handling - request has an output stream.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01017
AuthM: Deferring handling of status {0} due to use of an output stream.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01018
AuthM: Handling status: {0} "{1}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01019
AuthM: Resending request with Authorization "{0}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01020
AuthM: Resending request with Proxy-Authorization "{0}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01021
AuthM: Not handling status {0} because finding no Authorization information.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01022
AuthM: Parsing {0} challenges:

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-01023
AuthM: Challenge {0}

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-02001
ContentEncMod: pushing gzip-input-stream

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-02002
ContentEncMod: pushing inflater-input-stream

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-02003
ContentEncMod: pushing uncompress-input-stream

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-02004
ContentEncMod: ignoring "identity" token

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-02005
ContentEncMod: Unknown content encoding "{0}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-03000
ContentMD5Mod: Received digest: "{0}" - pushing md5-check-stream

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-03001
ContentMD5Mod: Expecting digest in trailer - pushing md5-check-stream

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-03003
ContentMD5Mod: successfully verifying hash

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04006
Cookie: Bad Set-Cookie header: "{0}". Finding no equal sign(=) for token starting at position {1}.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04007
Cookie: Ignoring cookie: {0}

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04008
Cookie: Bad Set-Cookie header: "{0}", invalid date "{1}"

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04009
Bad Set-Cookie header: "{0}", Max-Age "{1}" is negative.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04011
Cookie: Bad Set-Cookie header: "{0}", domain is empty - ignoring domain.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04012
Cookie: Bad Set-Cookie header: "{0}", current domain "{1}" does not match given parsed "{2}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04013
Cookie: Bad Set-Cookie header: "{0}", domain attribute "{1}" is not .local and does not have at least two dots.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04014
Cookie: Bad Set-Cookie header: "{0}", domain attribute "{1}" is more than one level below current domain {2}.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04015
Cookie2: Bad Set-Cookie2 header: "{0}", path "{1}" is not a prefix of the request URI "{2}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04016
Cookie2: Bad Set-Cookie2 header: "{0}", domain "{1}" is not ".local" and does not contain two "."s.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04017
Cookie2: Bad Set-Cookie2 header: "{0}", domain "{1}" does not match current host "{2}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04018
Cookie2: Bad Set-Cookie2 header: "{0}", domain "{1}" is more than one dot(.) away from host "{2}".

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04019
Cookie2: Bad Set-Cookie2 header: "{0}", port list does not include current port {1}.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-04020
Cookie: TLD, "{0}", does not start with ".", so it was removed from extendedTLDs.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-05000
Not handling status {0} {1} because exceeding maximum number of retries.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-05001
IOE closing InputStream for status 411: {0}

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-09000
HTTPConnection instance {0} has chunking enabled: {1}.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-09001
HTTPConnection instance {0} has chunk size set to {1}.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12000
Setting Maximum Authorization retries to {0}.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12001
"{0}" is enabled

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12002
"{0}" is disabled

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12003
Version: {0}

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12004
Enabling deferred handling of responses to streamed requests.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12005
Setting Socket Idle Timeout to {0} seconds.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12006
Adding module {0}.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12007
Adding module {0} to {1} list.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12008
Removing module {0} from {1} list.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12009
Default HTTP proxy set to {0}:{1,number,0}.

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12010
Setting Socket Connection Timeout to {0} milliseconds

Category:
Requests/Responses

Cause:

Action:

J2EE HTTPC-12011
Setting Socket Read Timeout to {0} milliseconds

Category:
Requests/Responses

Cause:

Action:

17
JPS-00001 to JPS-90642

JPS-00001
The method {0} is not supported.

Category:
Requests/Responses

Cause:
An unsupported method was used.

Action:
This operation is not supported. It cannot be used.

JPS-00003
The HTTP response callback is null.

Category:
Session

Cause:
HTTP response callback was null.

Action:
Check the log files and provide a valid HTTP response callback.

JPS-00004
The HTTP response is null.

Category:
Session

Cause:
HTTP response was null.

Action:
Check the log files and provide a valid HTTP response.

JPS-00005
HTTP request callback is null.

Category:
Session

Cause:
HTTP request callback was null.

Action:
Check the log files and provide a valid HTTP request callback.

JPS-00006
The HTTP request is null.

Category:
Session

Cause:
HTTP request was null.

Action:
Check the log files and provide a valid HTTP request.

JPS-00007
Cannot find an application ID.

Category:
Session

Cause:

Action:

JPS-00008
The application ID {0} is invalid.

Category:
Configuration

Cause:
Application ID was NULL.

Action:
Provide a valid application ID.

JPS-00009
The subject is read-only, and it cannot modified.

Category:
Requests/Responses

Cause:
Attempted to modify a read-only subject.

Action:
A read-only subject cannot be modified.

JPS-00010
A JPS context is not available in the callback handler.

Category:
Session

Cause:
A context was not available from callback handler.

Action:
Check configuration in jps-config.xml.

JPS-00011
The service instance {0} already exists.

Category:
Configuration

Cause:
The named service instance was already in use.

Action:
Use a different name for this service instance.

JPS-00012
The service instance {0} is missing.

Category:
Configuration

Cause:
The service instance with the name {0} was not found.

Action:
Ensure the service instance name is present in the file jps-config.xml.

JPS-00013
The login module {0} already exists.

Category:
Configuration

Cause:
The login module with the name {0} was already present.

Action:
Ensure the login module name is correct.

JPS-00014
The login module with {0} is missing.

Category:
Configuration

Cause:
The login module with the name {0} did not exist.

Action:
Ensure the login module name is correct.

JPS-00015
All available service instance names are already in use.

Category:
Configuration

Cause:
All service instance names were in use.

Action:
Remove unwanted service instances from jps-config.xml.

JPS-00016
All available service provider names are already in use.

Category:
Configuration

Cause:
All service provider names were in use.

Action:
Remove unwanted service providers form jps-config.xml.

JPS-00017
The LDAP type is invalid.

Category:
Configuration

Cause:
An invalid LDAP type was specified.

Action:
Provide a valid LDAP type. Valid types are XML, OID, ACTIVE_DIRECTORY, IPLANET, OUD and OVD. See the documentation for details.

JPS-00018
The keystore path {0} is null or invalid.

Category:
Configuration

Cause:
Keystore path was null.

Action:
Provide a valid keystore path.

JPS-00019
The key type {0} is not supported.

Category:
Configuration

Cause:
Invalid key type was provided.

Action:
Provide a valid key type.

JPS-00020
LDAP URL {0} is null or invalid.

Category:
Configuration

Cause:
Invalid or null LDAP URL was provided.

Action:
Provide a valid LDAP URL.

JPS-00021
An Object named {0} does not exist.

Category:
Configuration

Cause:
Object with the name {0} did not exist.

Action:
Verify that the object name is valid and exists.

JPS-00022
Callback handler missing for this login module request.

Category:
Requests/Responses

Cause:
The callback handler was null.

Action:
Provide an appropriate callback handler to invoke this login module.

JPS-00023
The callback used for this operation has no HTTP request value.

Category:
Requests/Responses

Cause:
The callback did not have a request method.

Action:
Verify that the callback is initialized with the correct HTTP request value.

JPS-00024
The callback used for this operation has no digest response object value.

Category:
Requests/Responses

Cause:
The callback did not have any digest response object.

Action:
Verify that the callback is initialized with the correct digest response value.

JPS-00025
The {0} subscriber {1} from the HTTP header is different from the subscriber configured by the identity store as {2}.

Category:
Configuration

Cause:
Found a subscriber mismatch.

Action:
Check the identity store subscriber configuration.

JPS-00026
The value "{0}" is invalid for {1}.

Category:
Requests/Responses

Cause:
An invalid value was provided for this application.

Action:
Provide the correct value for the application.

JPS-00027
There was an internal error: {0}

Category:
Requests/Responses

Cause:
Internal system error was found.

Action:
See the log files or contact the system administrator.

JPS-00028
The property runas.mode is deprecated and supported only for backward compatibility.

Category:
Requests/Responses

Cause:
The property runas.mode has been deprecated.

Action:
Use instead the oracle.security.jps.jaas.mode property in jps-config.xml.

JPS-00029
The audit service initialization failed for the application {0}. Reason {1}.

Category:
Configuration

Cause:
Audit service failed.

Action:
Check the audit service configuration in jps-config.xml.

JPS-00030
Cannot complete exist operation.

Category:
Configuration

Cause:
Could not find entity.

Action:
Verify that the entity exist.

JPS-00031
Cannot load the required class {0}. Reason {1}.

Category:
Upgrade

Cause:
Could not load a class.

Action:
Ensure the class is in the class path.

JPS-00032
The migration cannot write directly to the specified LDAP identity store; specify an alternate LDIF file to create.

Category:
Upgrade

Cause:
Could not perform a direct LDAP write operation.

Action:
See the log files for details.

JPS-00033
The direct policy store should be XML-based, and it can be specified as an XML file or as an input stream.

Category:
Upgrade

Cause:
The policy store specification was invalid.

Action:
Check the policy store specification.

JPS-00034
Cannot find the application context.

Category:
Session

Cause:
A context was not available for the application.

Action:
Check the jps-config.xml configuration.

JPS-00035
The WSS digest value {0} is invalid.

Category:
Requests/Responses

Cause:
Found missing WSS digest value in callback.

Action:
Verify that the callback has a valid WSS digest value.

JPS-00036
The WSS digest nonce {0} is invalid.

Category:
Requests/Responses

Cause:
Found missing WSS digest nonce in callback.

Action:
Verify that the callback has a valid WSS digest nonce.

JPS-00037
The WSS digest created {0} is invalid.

Category:
Requests/Responses

Cause:
Found missing WSS digest created in callback.

Action:
Verify that the callback has a valid WSS digest created.

JPS-00038
Cannot create or retrieve a ContextFactory.

Category:
Other

Cause:
Cannot retrieve or create a JPS ContextFactory.

Action:
Check jps-config.xml for correctness.

JPS-00039
The service instance with provider {0} and name {1} is missing.

Category:
Configuration

Cause:
A service instance configuration was missing.

Action:
Check the service instance configuration.

JPS-00040
The JPS audit component events file {0} is missing or invalid.

Category:
Other

Cause:
Cannot find the audit component events file.

Action:
Make sure the audit component events file is available and valid.

JPS-00041
Cannot load the JpsAdminService class.

Category:
Other

Cause:
The class JpsAdminService or a dependent class could not be loaded.

Action:
Review the cause to resolve the error.

JPS-00042
The LDAP connection pool provider {0} is not valid; the supported providers are JNDI or IDM. If unspecified, it defaults to UCP/JNDI provider.

Category:
Configuration

Cause:
The connection.pool.provider.type property value was invalid.

Action:
Configure a supported connection.pool.provider.type value, or use the default provider by not setting the connection.pool.provider.type property.

JPS-00043
Cannot establish an LDAP connection after {0} attempts.

Category:
Requests/Responses

Cause:
The connection could not be established.

Action:
Check the LDAP configuration.

JPS-00044
The LDAP URL format must be ldap://<host>:<port> or ldaps://<host>:<port>; but found {0}.

Category:
Configuration

Cause:
Invalid LDAP URL format was found.

Action:
The format of the LDAP URL must be ldap://<host>:<port> or ldaps://<host>:<port> format.

JPS-00045
The LDAP principal {0} is invalid.

Category:
Configuration

Cause:
The LDAP principal was invalid.

Action:
Provide a correct value for principal.

JPS-00046
The LDAP credential is invalid.

Category:
Configuration

Cause:
The LDAP credential was invalid.

Action:
Provide the correct credential value.

JPS-00047
The Subject parameter cannot be null.

Category:
Programmatic

Cause:
The supplied parameter was null.

Action:
Check the Subject parameter supplied in the method call.

JPS-00048
Principals are missing in the Subject.

Category:
Programmatic

Cause:
No principals were not found in the Subject.

Action:
Verify that the supplied Subject contains principals.

JPS-00049
The authenticated user principal is missing in the Subject.

Category:
Programmatic

Cause:
Authenticated user principal was not found in the Subject.

Action:
Verify that the supplied Subject contains an authenticated user principal.

JPS-00050
Invalid Subject parameter supplied.

Category:
Programmatic

Cause:
The Subject contained an anonymous user principal and an authenticated user principal.

Action:
Ensure that the Subject does not contain the anonymous user principal.

JPS-00051
The oracle.security.jps.config property not set.

Category:
Upgrade

Cause:
The oracle.security.jps.config property was not set.

Action:
Set the oracle.security.jps.config property to an appropriate value.

JPS-00052
Failed to Refresh Audit Service with new configuration.

Category:
Configuration

Cause:
Failed to reload the audit configuration.

Action:
Check the audit configuration file to see if the lastest changes are valid.

JPS-00053
Component events file is missing for {0} at {1}.

Category:
Configuration

Cause:
The component events file for the given component type was missing.

Action:
Verify that the properties set for the component files are correct in jps-config.xml.

JPS-00054
Failed to create the auditor for {0}.

Category:
Configuration

Cause:
Failed to create the auditor object.

Action:
Ensure that the component events file is not missing or corrupt and check the log files additional errors.

JPS-00055
Bootstrap credential store service is not initialized for the service configurator.

Category:
Programmatic

Cause:
The bootstrap credetial store service was not initialised.

Action:
Make sure the bootstrap credetial store service is initialized before any other services.

JPS-00056
Failed to create identity store service instance {0}. Reason: {1}.

Category:
Configuration

Cause:
Failed to create identity store service instance {0}. Cause: {1}.

Action:
Check the log files to resolve the error.

JPS-00057
Failed to set OutputProperty for indent or XML encoding. Reason {0}.

Category:
Configuration

Cause:
Failed to setOutputProperty for indent or XML encoding. Cause: {0}

Action:
Check the XML Transformer implementation.

JPS-00058
Failed to set XML output encoding to UTF-8 in OutputStreamWriter. Reason {0}.

Category:
Configuration

Cause:
Failed to set XML output encoding to UTF-8 in OutputStreamWriter. Cause: {0}

Action:
Check the JDK OutputStreamWriter supported encodings.

JPS-00059
The specified enterprise identity is null or invalid.

Category:
Configuration

Cause:
An enterprise identity provided was null or invalid

Action:
Provide a valid enterprise identity value.

JPS-00060
The specified enterprise identity {0} is not found in identity store.

Category:
Configuration

Cause:
The specified enterprise identity {0} was not found in the identity store.

Action:
Provide a valid enterprise identity value.

JPS-00061
No platform specific factory is found to create the platform principals. Check errors in the log files.

Category:
Configuration

Cause:
No platform specific factory was found to create platform principals.

Action:
Check the log files for the errors.

JPS-00062
No identity store associated with policy store found.

Category:
Configuration

Cause:
No identity store associate with policy store found

Action:
Contact system administrator

JPS-00063
Jps servlet filter creation failed. Reason: {0}.

Category:
Configuration

Cause:
Jps Servlet Filter creation failed

Action:
Contact system administrator

JPS-00064
Jps ejb interceptor creation failed. Reason: {0}.

Category:
Configuration

Cause:
Jps EJB Interceptor creation failed

Action:
Contact system administrator

JPS-00065
Jps platform factory creation failed. Reason: {0}.

Category:
Configuration

Cause:
Jps Platform Factory creation failed

Action:
Contact system administrator

JPS-00066
Jps property value retrieval failed. Reason: {0}.

Category:
Configuration

Cause:
Jps property value retrieval failed

Action:
Check the property values in jps configuration files

JPS-00068
Ldap security checking failed. The LDAP url should start with ldaps and oracle.ldap.wltloc system property should be set. Reason : {0}.

Category:
Security

Cause:
Is LDAP secure failed

Action:
Contact system administrator

JPS-00069
Ldap credential store provider missing.

Category:
Security

Cause:
LDAP credential provider missed

Action:
Ensure ldap credential store provider is configured

JPS-00070
Ldap policy store provider missing.

Category:
Security

Cause:
LDAP policy store provider missing

Action:
Ensure ldap policy store is configured

JPS-00071
Ldap bootstrap credential retrieval failed. Reason:{0}.

Category:
Security

Cause:
Retrieval of bootstrap credential failed

Action:
Check the credential store configuration for credential types, maps and key

JPS-00072
Policy schema upgrade not required. Store Schema version {0} is compatible to the seed schema version {1}

Category:
Configuration

Cause:
Comparison of policy schema version in the store against to seed schema version.

Action:
No action required

JPS-00073
Policy store schema version not found

Category:
Configuration

Cause:
Trying to determine version of the policy schema in the store

Action:
Contact Oracle Support Services.

JPS-00074
Policy store schema version {0} is less than the latest schema version {1}, upgrade the Policy store schema to latest version.

Category:
Configuration

Cause:
Comparison of the Policy schema version in the store against the schema to seed

Action:
No action required

JPS-00075
Unable to query Policy store schema version under "{0}", Cause {1}

Category:
Configuration

Cause:
Query of Policy schema from the store failed

Action:
Confirm the Policy store schema containers are present in the store

JPS-00076
Policy schema version set to {0}

Category:
Configuration

Cause:
Version of the policy schema has been set in the store

Action:
No action required

JPS-00077
Setting version of policy schema in the store failed. Cause {0}

Category:
Configuration

Cause:
Unexpected error occurred while setting the version of the Policy schema in the store

Action:
Confirm the container is present in the store and caller has sufficient privileges to perform this operation

JPS-00078
Credential store schema upgrade not required. Store Schema version {0} is compatible to the seed schema version {1}

Category:
Configuration

Cause:
Comparison of Credential schema version in the store against the seed schema version.

Action:
No action required

JPS-00079
Credential store schema version not found

Category:
Configuration

Cause:
Check if the DN exists, or if the Credential Store schema version attribute is present at the specificied location

Action:
Contact Oracle Support Services.

JPS-00080
Credential store schema version {0} is less than the latest schema version {1}, upgrade the Credential store schema to latest version.

Category:
Configuration

Cause:
Comparison of the Credential schema version in the store against the schema to seed

Action:
No action required

JPS-00081
Unable to query Credential store schema version under "{0}", Cause {1}

Category:
Configuration

Cause:
Query of Credential schema from store store failed

Action:
Confirm the Credential store schema container in the store is present

JPS-00082
Credential schema version set to {0}

Category:
Configuration

Cause:
Version of the credential schema has been set in the store

Action:
No action required

JPS-00083
Setting version of credential schema in the store failed. Cause {0}

Category:
Configuration

Cause:
Unexpected error occurred while setting the version of the credential schema in the store

Action:
Confirm the container is present in the store and caller has sufficient privileges to perform this operation

JPS-00084
IOException raised from FileLocker {0}.

Category:
Other

Cause:
Closing IO objects in FileLocker

Action:
Check the file system for access privileges and disk space availability.

JPS-00085
OID version is unavailable.

Category:
Other

Cause:
OID version is unavalable

Action:
Check the ldap url against the server type passed.

JPS-00086
Error while encoding search string: {0} to UTF-8 encoding

Category:
Other

Cause:
Unable to encode user string to UTF-8 encoding

Action:
Check the search string.

JPS-00087
The subject parameter is null.

Category:
Security

Cause:
The subject parameter is null

Action:
Make sure the subject parameter is not null

JPS-00088
The user name parameter is null.

Category:
Security

Cause:
The user name parameter is null

Action:
Make sure the user name parameter is not null

JPS-00089
The subject from the current AccessControlContext is null.

Category:
Security

Cause:
No subject is associated with the current AccessControlContext.

Action:
Ensure that the subject is associated with the current AccessControlContext.

JPS-00090
Failed to create policy store service instance {0}. Cause: {1}.

Category:
Configuration

Cause:
Failed to create policy store service instance {0}. Cause: {1}.

Action:
Check the log files to resolve the error.

JPS-00091
No {0} available.

Category:
Requests/Responses

Cause:
No {0} available.

Action:
Contact the administrator.

JPS-00092
The ldap service was null.

Category:
Security

Cause:
The ldap service was null.

Action:
Ensure the ldap service is not null.

JPS-00093
Class {0} was not type of {1}.

Category:
Security

Cause:
Class {0} was not type of {1}.

Action:
Ensure class name is correct.

JPS-00094
Failed to parse digest response.

Category:
Configuration

Cause:

Action:

JPS-00095
{0} system properties not set.

Category:
Configuration

Cause:
System properties {0} not set.

Action:
Set the system properties.

JPS-00096
No {0} defined for {1}.

Category:
Configuration

Cause:
No {0} defined for {1}.

Action:
Defined the specified object.

JPS-00097
{0} missing in message : {1}.

Category:
Configuration

Cause:
{0} missing in message : {1}.

Action:
Check the input.

JPS-00098
Duplicate error message.

Category:
Configuration

Cause:
Duplicate error message.

Action:
Check the input.

JPS-00099
{0} already exists.

Category:
Configuration

Cause:
{0} already exists.

Action:
Check the input.

JPS-00100
Failed to instantiate {0}.

Category:
Configuration

Cause:
Failed to instantiate {0}.

Action:
Check the object type.

JPS-00101
{0} not match {1}.

Category:
Configuration

Cause:
{0} not match with {1}.

Action:
Check the object type.

JPS-00102
Unhandled entry {0}

Category:
Configuration

Cause:
Unhandled entry {0}.

Action:
Check the entry.

JPS-00103
Invalid login module type {0}.

Category:
Configuration

Cause:
Invalid login module type {0}.

Action:
Use valid login module type.

JPS-00104
System policy does not exist.

Category:
Configuration

Cause:
System policy does not exist.

Action:
Ensure system policy exist.

JPS-00105
Failed to create temp dir {0}.

Category:
Configuration

Cause:
Failed to create temp dir {0}.

Action:
Check the log for more details.

JPS-00106
InputStream has no more data to read.

Category:
Configuration

Cause:
InputStream had no more data to read.

Action:
Check the log for more details.

JPS-00107
{0} invoked.

Category:
Security

Cause:

Action:

JPS-00108
Event {0} was ignored.

Category:
Security

Cause:

Action:

JPS-00109
Overwriting credentials is allowed at application credential store migration with Weblogic server running in {0} and system property {1} set to {2}.

Category:
Security

Cause:

Action:

JPS-00110
Failed to decode {0}. Reason {1}.

Category:
Security

Cause:
Failed to decode {0}. Reason: {1}.

Action:
Check log for more details.

JPS-00111
Current timer interval ({0} seconds) is too short.

Category:
Security

Cause:
Current timer interval ({0} seconds) is too short.

Action:
Please set a longer interval in the configuration file.

JPS-00112
Set property {0} to value {1}.

Category:
Security

Cause:
Set property {0} to value {1}.

Action:
Check log for more details.

JPS-00113
Failed to parse condition {0}. Reason {1}.

Category:
Security

Cause:
Failed to parse condition {0}. Reason {1}.

Action:
Check log for more details.

JPS-00114
Failed to load data file {0}.

Category:
Security

Cause:
Failed to load data file {0}.

Action:
Please check file location.

JPS-00115
Failed to modify JPS Schema.

Category:
Security

Cause:
Failed to modify JPS Schema.

Action:
Check log for more details.

JPS-00116
Failed to read JPS Schema.

Category:
Security

Cause:
Failed to read JPS Schema.

Action:
Check log for more details.

JPS-00117
Failed to delete System Policy name {0}. Reason {1}.

Category:
Security

Cause:
Failed to delete System Policy name {0}. Reason {1}.

Action:
Check log for more details.

JPS-00118
{0} not found.

Category:
Security

Cause:
{0} not found.

Action:
Check log for more details.

JPS-00119
Failed to create ResourceEntry name: {0}, action: {1}, cause: {2}.

Category:
Security

Cause:
Failed to create ResourceEntry name: {0}, action: {1}, cause: {2}.

Action:
Check log for more details.

JPS-00120
Failed to seed attribute {0}, ldap object class {1}.

Category:
Configuration

Cause:
Failed to seed attribute {0}, ldap object class {1}.

Action:
Check the LDAP configuration to resolve the error.

JPS-00121
Failed to parse LDIF record {0}. Reason: {1}.

Category:
Configuration

Cause:
Failed to parse LDIF record {0}. Reason: {1}.

Action:
Check the LDAP configuration to resolve the error.

JPS-00122
Farm DN {0} does not exist.

Category:
Configuration

Cause:
Farm DN {0} does not exist.

Action:
Ensure farm DN is valid.

JPS-00123
RDN {0} not found under farm {1}.

Category:
Configuration

Cause:
RDN {0} not found under farm {1}.

Action:
Check LDAP server type.

JPS-00124
{0} is not supported.

Category:
Configuration

Cause:
{0} is not supported.

Action:
Use a valid type.

JPS-00125
Property {0} was null.

Category:
Requests/Responses

Cause:
Property {0} was null.

Action:
Ensure property is not null.

JPS-00126
Overwriting credentials is not allowed at application credential store migration with Weblogic server running in {0} and system property {1} set to {2}.

Category:
Security

Cause:

Action:

JPS-00127
Failed to create igf service instance {0}. Reason: {1}.

Category:
Configuration

Cause:
Failed to create igf service instance {0}. Cause: {1}.

Action:
Check the log files to resolve the error.

JPS-00128
Keystore schema upgrade not required. Store Schema version {0} is compatible to the seed schema version {1}

Category:
Configuration

Cause:
Comparison of Keystore schema version in the store against the seed schema version.

Action:
No action required

JPS-00129
Keystore schema version not found

Category:
Configuration

Cause:
Check if the DN exists, or if the Keystore schema version attribute is present at the specificied location

Action:
Contact Oracle Support Services.

JPS-00130
Keystore schema version {0} is less than the latest schema version {1}, upgrade the Keystore schema to latest version.

Category:
Configuration

Cause:
Comparison of the Keystore schema version in the store against the schema to seed

Action:
No action required

JPS-00131
Unable to query Keystore schema version under "{0}", Cause {1}

Category:
Configuration

Cause:
Query of Keystore schema from store store failed

Action:
Confirm the Keystore schema container in the store is present

JPS-00132
Keystore schema version set to {0}

Category:
Configuration

Cause:
Version of the keystore schema has been set in the store

Action:
No action required

JPS-00133
Setting version of keystore schema in the store failed. Cause {0}

Category:
Configuration

Cause:
Unexpected error occurred while setting the version of the keystore schema in the store

Action:
Confirm the container is present in the store and caller has sufficient privileges to perform this operation

JPS-00134
The offline deployment staging directory {0} does not exist.

Category:
Deployment

Cause:
The cause may be that the product was installed inproperly.

Action:
Install the product properly.

JPS-00135
Exception occurs on saving ear file {0}.

Category:
Deployment

Cause:
The cause may be due to bad ear file or insufficient permission.

Action:
Check the ear file and the file system permissiion.

JPS-00136
Exception occurs on saving offline deployment property file in application directory {0}.

Category:
Deployment

Cause:
The cause may be due to insufficient permission.

Action:
Check the file system permissiion.

JPS-00137
Found offline deployed app {0}.

Category:
Deployment

Cause:

Action:

JPS-00138
Exception occurs on opening the staging application in {0}.

Category:
Deployment

Cause:
This may be caused by bad .ear file on the disk.

Action:
Check the .ear file on the disk.

JPS-00139
Exception occurs on loading the property file of the staging application in {0}.

Category:
Deployment

Cause:
Failed to open the property file.

Action:
Check the property file on the disk.

JPS-00140
Failed to delete the staging app {0}. Migration flag file created.

Category:
Deployment

Cause:

Action:

JPS-00141
Cannot handle offline deployed application due to the required system property {0} is not set.

Category:
Deployment

Cause:
The cause may be that the product was installed inproperly.

Action:
Install the product properly.

JPS-00142
No opss-application.xml found.

Category:
Deployment

Cause:

Action:

JPS-00143
Error on migrating security artifacts.

Category:
Deployment

Cause:
Error on migrating security artifacts.

Action:
Check security related files in your application, such as opss-application.xml, jazn-data.xml, cwallet.sso, etc.

JPS-00144
Error on opening ear file {0}.

Category:
Deployment

Cause:
Error on opening ear file.

Action:
Check the ear file.

JPS-00145
Found no installed application at {0}.

Category:
Deployment

Cause:
Found no installed application at {0}.

Action:
Check the installed application at {0}.

JPS-00146
Failed to create identity store service instance {0}. Reason: the service does not enable the virtualizes flag, but references other service instance.

Category:
Configuration

Cause:
Failed to create identity store service instance {0}. Cause: the service does not enable the virtualize flag, but references other service instance.

Action:
Either make the virtualize flag true, or directly define the ldap configuration instead of using service reference

JPS-00147
Keystore re-association not supported.

Category:
Configuration

Cause:
Configuration of key store was not suitable for re-association.

Action:
Confirm the key store configuration is updated.

JPS-00148
Jps JBoss signing key seeded.

Category:
Security

Cause:

Action:

JPS-00149
Jps JBoss signing key already exists. Seeding ignored.

Category:
Security

Cause:

Action:

JPS-00150
Key 1 and Key 2 are no longer supported for system parameter -Djps.subject.cache.key, please use key 4 (default), 3, or 5 (fastest).

Category:
Security

Cause:

Action:

JPS-00151
Audit store instantiation failure, type: {0} reason: {1}

Category:
Configuration

Cause:
Audit metadata store failed to be instantiated, type: {0}, reason: {1}

Action:
Check the audit service configuration in jps-config.xml.

JPS-00152
Component not registered, name: {0}

Category:
Configuration

Cause:
Component {0} not registered and no audit configuration found.

Action:
Register component with audit service.

JPS-00153
The principal {0} is invalid.

Category:
Configuration

Cause:
The principal is invalid.

Action:
Provide a correct value for principal.

JPS-00154
The rule condition {0} is invalid.

Category:
Configuration

Cause:
The rule condition function is invalid.

Action:
Provide a correct value for rule condition function.

JPS-00155
Audit metadata store is not instantiated in audit service.

Category:
Configuration

Cause:
Audit metadata store is not instantiated.

Action:
Verify that the audit store properties for audit service are correct in jps-config.xml.

JPS-00156
Audit metadata store type {0} is invalid

Category:
Configuration

Cause:
Audit metadata store type {0} is invalid

Action:
Check the audit service configuration in jps-config.xml.

JPS-00157
The DN {0} was invalid LdapName format, see javax.naming.ldap.LdapName

Category:
Configuration

Cause:
The DN {0} was invalid LdapName format, see javax.naming.ldap.LdapName

Action:
Ensure property in format of javax.naming.ldap.LdapName.

JPS-00158
Audit store schema upgrade not required. Store Schema version {0} is compatible to the seed schema version {1}

Category:
Configuration

Cause:
Comparison of Audit schema version in the store against the seed schema version.

Action:
No action required

JPS-00159
Audit store schema version not found

Category:
Configuration

Cause:
Check if the DN exists, or if the Audit Store schema version attribute is present at the specificied location

Action:
Contact Oracle Support Services.

JPS-00160
Audit store schema version {0} is less than the latest schema version {1}, upgrade the Audit store schema to latest version.

Category:
Configuration

Cause:
Comparison of the Audit schema version in the store against the schema to seed

Action:
No action required

JPS-00161
Unable to query Audit store schema version under "{0}", Cause {1}

Category:
Configuration

Cause:
Query of Audit schema from store store failed

Action:
Confirm the Audit store schema container in the store is present

JPS-00162
Audit schema version set to {0}

Category:
Configuration

Cause:
Version of the audit schema has been set in the store

Action:
No action required

JPS-00163
Setting version of audit schema in the store failed. Cause {0}

Category:
Configuration

Cause:
Unexpected error occurred while setting the version of the audit schema in the store

Action:
Confirm the container is present in the store and caller has sufficient privileges to perform this operation

JPS-00164
Audit store re-association not supported.

Category:
Configuration

Cause:
Configuration of audit store was not suitable for re-association.

Action:
Confirm the audit store configuration is updated.

JPS-00165
Failed to reload component {0} runtime policy with error message {1}.

Category:
Other

Cause:
Failed to reload component runtime policy.

Action:
Check component run policy and custom fitler preset definition.

JPS-00166
Failed to retrieve Embedded LDAP store information.

Category:
Configuration

Cause:
Failed to retrieve embedded ldap store information.

Action:
Check the log files to resolve the error.

JPS-00167
Invalid xml content was found. {0} Location: {1}.

Category:
Security

Cause:
Invalid xml content was found. {0} Location: {1}.

Action:
Fix the invalid xml elements according to the xsd schema definition.

JPS-00168
OID server version {0} is not supported

Category:
Other

Cause:
OID server version {0} is not supported

Action:
Check the support matrix.

JPS-00169
Cannot get server log directory. Reason: {0}.

Category:
Security

Cause:
Cannot get server log directory. Reason: {0}.

Action:
Check server configuration.

JPS-00170
Initializing OPSS Java Policy Provider.

Category:
Configuration

Cause:

Action:

JPS-00171
OPSS Java Policy Provider initialized.

Category:
Configuration

Cause:

Action:

JPS-00172
OPSS Java Policy Provider is set as the system-wide Policy object.

Category:
Configuration

Cause:

Action:

JPS-00173
OPSS Java Policy Provider is already set as the system-wide Policy object. Skipped setting the system-wide Policy object.

Category:
Configuration

Cause:

Action:

JPS-00174
Failed to create the enterprise user principal for "{0}". Reason: {1}.

Category:
Security

Cause:
Error on creating the enterprise user principal.

Action:
Check the configuration.

JPS-00175
Failed to create the enterprise group principal for "{0}". Reason: {1}.

Category:
Security

Cause:
Error on creating the enterprise group principal.

Action:
Check the configuration.

JPS-00176
Service instance of {0} is in state {1} that does not allow invocation of {2}.

Category:
Security

Cause:
Service instance is in a state that does not allow current invocation.

Action:
Only invoke service instance's method when it is in right state.

JPS-00177
Failed to clean up application security artifacts.

Category:
Deployment

Cause:
Error on cleaning up application security artifacts.

Action:
Check the configuration.

JPS-00178
Service provider " {0} " not available from configuration service.

Category:
Security

Cause:
Service provider not available.

Action:
Check the configuration.

JPS-00179
Service context configuration for " {0} " not available from configuration service.

Category:
Security

Cause:
Service context configuration not available.

Action:
Check the configuration.

JPS-00180
Failed to create service context for tenant ID " {0} ".

Category:
Security

Cause:
Failed to create service context.

Action:
Check the configuration.

JPS-00181
Your search criteria (current search iterator) has expired(stale). Start a new search.

Category:
Other

Cause:
Your search criteria (current search iterator) has expired(stale).

Action:
Start a new search.

JPS-00182
Method getView for JpsConfigurationP was not run for RuntimeViewAdapter object before calling getServiceProperties() of ServiceInstanceDescriptorAdapter

Category:
Configuration

Cause:
Method getView for JpsConfigurationP was not run for RuntimeViewAdapter object before calling getServiceProperties() of ServiceInstanceDescriptorAdapter

Action:
Call method getView for JpsConfigurationP on RuntimeViewAdapter object before calling getServiceProperties() of ServiceInstanceDescriptorAdapter

JPS-00183
Jps diagnostics started.

Category:
Other

Cause:

Action:

JPS-00184
Jps diagnostics startup failed.

Category:
Other

Cause:
Failed to start JPS diagnostics.

Action:
Check the configuration.

JPS-00185
Tenant Context is not set

Category:
Security

Cause:
Tenant Context is not set

Action:
Check the configuration.

JPS-00186
Failed to validate the Tenant Context for the tenant with ID " {0} ".

Category:
Security

Cause:
Tenant Context is Invalid

Action:
Only invoke services that you signed up for

JPS-00187
A dump to execute JPS diagnostic tests.

Category:
Other

Cause:

Action:

JPS-00188
Dumps security information in current execution thread, such as application name, subject, etc.

Category:
Other

Cause:

Action:

JPS-00189
OPSS diagnostic test to execute.

Category:
Other

Cause:

Action:

JPS-00190
Tenant ID cannot be found from user "{0}" profile.

Category:
Other

Cause:
Tenant ID cannot be found from authenticated user profile.

Action:
Check user profile.

JPS-00191
Identity context not found.

Category:
Other

Cause:
IdentityContext not found from request attributes.

Action:
OAM IAP.

JPS-00192
Service instance not found for the service type.

Category:
Security

Cause:
Service instance not available for the service type.

Action:
Check the configuration.

JPS-00193
Service instance "{0}" cannot be instantiated. Reason: {1}.

Category:
Security

Cause:
Service instance cannot be instantiated.

Action:
Check the configuration.

JPS-00194
OPSS diagnostic test parameters to execute. Example: username=user1;groupname=group1

Category:
Other

Cause:

Action:

JPS-00195
Dumps properties used to initialize User/Role Api when User/Role Api initialization fails.

Category:
Other

Cause:

Action:

JPS-00196
Jps started.

Category:
Security

Cause:

Action:

JPS-00197
Failed to migrate application credential during deployment.

Category:
Configuration

Cause:
Migration of Application credential failed during deployment.

Action:
Check the server logs for details.

JPS-00198
Custom product logger set (class: {0}, name: {1}). All JPS messages would be redirected to this logger.

Category:
Configuration

Cause:

Action:

JPS-00199
JpsLogger has initialized Loggers. Cannot set custom product Logger after initializing loggers.

Category:
Configuration

Cause:
Loggers have already been initialized.

Action:
Set product logger before creating JpsLogger instance.

JPS-00200
Invalid path. Please make sure the provided config path is a directory.

Category:
Configuration

Cause:

Action:

JPS-00201
Invalid path. Please make sure the provided config directory has jps-config.xml and jps-config-jse.xml inside it.

Category:
Configuration

Cause:

Action:

JPS-00202
Jps post service activation operations started.

Category:
Security

Cause:

Action:

JPS-00203
Upgrade of file based domain not supported

Category:
Configuration

Cause:
Upgrading of file based domain not supported

Action:
Please move the file based domain to database based domain, then run reconfiguration

JPS-00204
Migrate source or destination store context lookup failure

Category:
Configuration

Cause:
Migrate source or destination context in migration could not be looked up.

Action:
Check the configuration file to verify service context settings

JPS-00205
Security store version configured is incompatible

Category:
Configuration

Cause:
Security store version configured is incompatible with this release.

Action:
Please use security store version 12.1.3 or lower

JPS-00206
Jps is already started.

Category:
Security

Cause:
Can not start Jps again since it is already started.

Action:
Please do not start JPS if it is already started

JPS-00207
Service context {0} is not in active state

Category:
Security

Cause:
Service context is not in active state.

Action:
Please check logs to see service context failure.

JPS-00208
Jps initializing.

Category:
Security

Cause:

Action:

JPS-00209
Jps startup failed.

Category:
Security

Cause:
Jps startup is failed due to some error.

Action:
Please check logs to see Jps startup failure.

JPS-00210
Jps inactive.

Category:
Security

Cause:

Action:

JPS-00211
Not supported platform type {0}.

Category:
Security

Cause:

Action:

JPS-00212
Error occurred while stopping jps due to: {0}.

Category:
Configuration

Cause:
Error occured while stopping the OPSS

Action:
Check the server logs for details.

JPS-00213
Parameter "{0}" cannot be null.

Category:
Data

Cause:
method parameter cannot be null

Action:
provide a non-null value for the parameter

JPS-00214
Operation "{0}" is not supported in OPSS Mode "{1}".

Category:
Configuration

Cause:
the invoked operation is not supported in JPS_API mode

Action:
set the OPSS Mode to one of COMPATIBLE or MULTIPLE

JPS-00215
executeAs: Switching SecurityContext from "{0}" to "{1}" is not permitted.

Category:
Configuration

Cause:
the requested SecurityContext Switch is not Permitted

Action:
Look at documentation for allowed context switches

JPS-00216
Failed to get a handle to the global audit service for tenant {0}.

Category:
Security

Cause:
Failed to get a handle to the global audit service

Action:
Check configuration

JPS-00217
The schema specified in {0} is already in use for security store. Please create a new schema.

Category:
Configuration

Cause:
The schema specified in {0} is already in use for security store.

Action:
Please create a new schema.

JPS-00218
Comparison of credential failed for map : {0}, key : {1}.

Category:
Requests/Responses

Cause:
Encryption key comparison failed.

Action:
Retry importEncryptionKey command or api.

JPS-00219
Expected keys not found in the credential map : {0}.

Category:
Requests/Responses

Cause:
Expected keys not found in the credential map

Action:
Verify the credential store content.

JPS-00220
Cannot find datasource definition {0}. Reason: {1}.

Category:
Security

Cause:
Cannot find datasource definition {0}. Reason: {1}.

Action:
Check weblogic configuration.

JPS-00221
Error occurred while resetting jps due to: {0}.

Category:
Configuration

Cause:
Error occured while resetting OPSS

Action:
Check the server logs for details.

JPS-00222
Jps is reset.

Category:
Security

Cause:

Action:

JPS-00223
Specified JPS context "{0}" not found

Category:
Security

Cause:
Specified JPS context not found

Action:
Check the input configuration that the correct context name is present and is the one supplied as input.

JPS-00224
Invalid inputted migration parameters "{0}"

Category:
Security

Cause:
Invalid inputted migration parameters

Action:
Check inputted migration parameters.

JPS-00225
Commmand: {0} is not supported.

Category:
Configuration

Cause:
Commmand: {0} is not supported.

Action:
Use a valid command. Try <command> --help for more information.

JPS-00226
Service setup check completed for configurator.

Category:
Process

Cause:
Service setup check completed for configurator.

Action:
No Action Required

JPS-00227
Completed the Migration of Policy Artifacts.

Category:
Upgrade

Cause:
Completed the Migration of Policy Artifacts.

Action:
No actions are required.

JPS-00228
Security store is not seeded with the schema.

Category:
Other

Cause:
Security store is not seeded with the schema.

Action:
Check the log files to resolve the warning.

JPS-00229
Trying to load the schema into the security store ...

Category:
Process

Cause:
Trying to load the schema into the security store ...

Action:
No action required.

JPS-00230
BootStrap Wallet file is created.

Category:
Programmatic

Cause:
BootStrap Wallet file is created.

Action:
No action required

JPS-00231
Completed the seeding of schema into the security store.

Category:
Other

Cause:
Completed the seeding of schema into the security store.

Action:
No action required.

JPS-00232
Successfully loaded the security store schema.

Category:
Process

Cause:
Successfully loaded the security store schema.

Action:
No action required.

JPS-00233
Migration of Policy Artifacts failed.

Category:
Upgrade

Cause:
Migration of Policy Artifacts failed.

Action:
Check the log files for details.

JPS-00234
Persist jps-config.xml to directory: {0} - done.

Category:
Configuration

Cause:
Persist jps-config.xml to directory: {0} - done.

Action:
No action Required.

JPS-00235
Persist jps-config-jse.xml to directory: {0} - done.

Category:
Configuration

Cause:
Persist jps-config-jse.xml to directory: {0} - done.

Action:
No action Required.

JPS-00236
Bootstrap key store service instance already present in bootstrap credential store context.

Category:
Process

Cause:
Bootstrap key store service instance already present in bootstrap credential store context.

Action:
No Action Required

JPS-00237
Adding keystore service instance to bootstrap context for the {0} file.

Category:
Process

Cause:
Adding keystore service instance to bootstrap context for the {0} file.

Action:
No Action Required

JPS-00238
Error in loading the property file.

Category:
Configuration

Cause:
Error in loading the property file.

Action:
Check the log files to resolve the error.

JPS-00239
Exception while updating the keystore service instance to bootstrap context for {0} file.

Category:
Process

Cause:
Exception while updating the keystore service instance to bootstrap context for {0} file.

Action:
Check the log files to resolve the error.

JPS-00240
JpsConfiguration object is not passed, not able to add Keystore service instance to Bootstrap context.

Category:
Configuration

Cause:
JpsConfiguration object is not passed, not able to add Keystore service instance to Bootstrap context.

Action:
Check the log files to resolve the error.

JPS-00241
No file based keystore service instance is found, not able to add Keystore service instance to Bootstrap context.

Category:
Configuration

Cause:
This operation is not supported in restricted-JRF domain

Action:
Please check document for supported operations in restricted-JRf domain

JPS-00242
This operation is not supported in restricted-JRF domain

Category:
Configuration

Cause:
No file based keystore service instance is found, not able to add Keystore service instance to Bootstrap context.

Action:
Check the log files to resolve the error.

JPS-00243
{0} cannot be started as JRF Executor serivce retrieval got failed.

Category:
Security

Cause:
{0} cannot be started as JRF Executor serivce retrieval got failed.

Action:
Check stack trace for more details.

JPS-00244
No audit log directory is set. Cannot perform audit operations for component {0}.

Category:
Configuration

Cause:
Failed to get audit log directory. Audit calls may fail.

Action:
Check if the audit log directory is set either in audit service properties or as a system property.

JPS-00245
No audit log directory is set. Disabling audit for component {0}.

Category:
Configuration

Cause:
Failed to get audit log directory.

Action:
Check if the audit log directory is set either in audit service properties or as a system property.

JPS-00246
new Startup().start() is required to be called before using OPSS API.

Category:
Configuration

Cause:
OPSS API is used without calling new JpsStartup().start() first.

Action:
Call new JpsStartup().start() before using OPSS API.

JPS-00247
Could not retrieve tenant context.

Category:
Configuration

Cause:
Tenant context could not be retrieved.

Action:
Ensure tenant has been provisioned.

JPS-00248
This JpsStartup object was cleaned up. To start OPSS again, need create a new instance of JpsStartup.

Category:
Configuration

Cause:
The start() method is called on an JpsStartup object that was cleaned up.

Action:
Create a new instance of JpsStartup, then call the start() method on it.

JPS-00249
Operation "{0}" can only be performed when OPSS is in state "{1}". Current state is {2}.

Category:
Configuration

Cause:
Operation "{0}" can only be performed when OPSS is in state "{1}". Current state is {2}.

Action:
Perform operation "{0}" only when OPSS is in state "{1}".

JPS-00250
OPSS is already pre-started.

Category:
Configuration

Cause:
preStart() is called when OPSS is already pre-started.

Action:
Do not call preStart() if OPSS is already pre-started.

JPS-00251
This JpsStartup object is already reset.

Category:
Configuration

Cause:
reset() on a JpsStartup object is called when the object is already reset.

Action:
Do not call reset() when the JpsStartup objet is already reset.

JPS-00252
The {0} operation starting for partition {1}.

Category:
Process

Cause:
Starting the operation for partition.

Action:
No Action Required

JPS-00253
The {0} operation completed for partition {1}.

Category:
Process

Cause:
Completed the operation for partition.

Action:
No Action Required

JPS-00254
Tenant services {0} successfully for partition {1}.

Category:
Process

Cause:
Tenant services operation done successfully for partition.

Action:
No Action Required

JPS-00255
JPS post service started.

Category:
Process

Cause:
JPS post service started.

Action:
No Action Required

JPS-00256
JPS default service started.

Category:
Process

Cause:
JPS default service started.

Action:
No Action Required

JPS-00257
JPS bootstrap service started.

Category:
Process

Cause:
JPS bootstrap service started.

Action:
No Action Required

JPS-00258
Bootstrap services are used by OPSS internally and clients should never need to directly read/write bootstrap credentials. If required, use Wlst or configuration management interfaces.

Category:
Configuration

Cause:
An attempt to obtain bootstrap context is made.

Action:
Use WLST commands like addBootstrapCredential /modifyBootstrapCredential if required.

JPS-00259
Cannot terminate OPSS service context for partition {0}. Reason {1}.

Category:
Configuration

Cause:
Cannot terminate OPSS service context for partition {0}. Reason {1}.

Action:
Check reason for detail

JPS-00260
Database access error. SQL state: {0}, error code: {1}.

Category:
Configuration

Cause:
Database access error. SQL state: {0}, error code: {1}.

Action:
Check log for detail.

JPS-00261
Invalid value for "order" : {0} in service instance reference {1}

Category:
Configuration

Cause:
Configuration is corrupt.

Action:
Correct the configuration

JPS-00262
Duplicate value for "order" : {0} in service instance reference {1}

Category:
Configuration

Cause:
Configuration is corrupt.

Action:
Correct the configuration

JPS-00263
Cannot modify read only artifacts

Category:
Requests/Responses

Cause:
An attempt to modify/delete read only artifacts has been made.

Action:
Read only artifacts cannot be modified at runtime.

JPS-00264
Database is disconnected. SQL state: {0}, error code: {1}.

Category:
Configuration

Cause:
Database is disconnected. SQL state: {0}, error code: {1}.

Action:
Check log for detail.

JPS-00265
executeAs: SecurityContext with name "{0}" does not exist

Category:
Configuration

Cause:
The requested SecurityContext does not exist

Action:
Input a valid SecurityContxt name

JPS-00266
System property oracle.net.tns_admin has been set, OPSS can not overwrite it.

Category:
Configuration

Cause:
System property oracle.net.tns_admin has been set, OPSS can not overwrite it.

Action:
Skip setting tns property

JPS-00267
Tenant context already exists - {0}.

Category:
Requests/Responses

Cause:
The tenant context already activated.

Action:
No actions are required.

JPS-00268
Tenant context not activated - {0}.

Category:
Requests/Responses

Cause:
The tenant context not activated.

Action:
No actions are required.

JPS-00269
Client name "{0}" is too long.

Category:
Other

Cause:
Client name is too long when calling opssRestClient to register a client.

Action:
Make client name shorter

JPS-00270
Datasource ID {0} from tenant context {1} conflicts with tenant context {2}.

Category:
Other

Cause:
Datasource ID from DataSourceCallback handler conflicts with existing tenant.

Action:
Make client name shorter

JPS-00271
Exception occurs during JpsStartup start. Reason {0}. Will retry {1} time(s) in next {2} seconds.

Category:
Other

Cause:
Exception occurs during JpsStartup start, will retry

Action:
Check cause of failure

JPS-00272
Exception occurs during JPS API "{0}" called. Reason {1}. Will retry {2} time(s) in next {3} seconds.

Category:
Other

Cause:
Exception occurs during JPS API call, will retry

Action:
Check cause of failure

JPS-00273
Tenant context activated - {0}.

Category:
Requests/Responses

Cause:
The tenant context activated.

Action:
No actions are required.

JPS-00274
Tenant context {0} activation failed. Error: {1}.

Category:
Requests/Responses

Cause:
The tenant context activation failed.

Action:
No actions are required.

JPS-00648
Operation is not supported - unable to set key entry for non-existent stripe and keystore.

Category:
Compliance

Cause:
Combining certs from two truststores into a single truststore failed

Action:
Look at the logs for any exceptions that could have caused this failure

JPS-00649
********** * Demonstration CA was found in use in this environment. * * This deployment may be vulnerable to security attacks. * * Replace the Demonstration CA with a custom CA immediately. *
****

Category:
Compliance

Cause:
Demonstration CA was found in use in a production environment.

Action:
Refer documentation to switch to a custom CA.

JPS-00650
Virtual KSS URI to aggregate multiple keystores already exists

Category:
Compliance

Cause:
The virtual KSS URI passed in already exists

Action:
Use a different virtual KSS URI

JPS-00651
Aggregation of multiple keystores pointed by virtual URI failed

Category:
Compliance

Cause:
Aggregation of Keystores pointed to by virtual URI failed

Action:
Check if the source Keystores pointed to by virtual URI are valid

JPS-00652
Cannot set or save entries in virtual keystore

Category:
Compliance

Cause:
Setting of an entry in a virtual Keystore failed

Action:
Entries cannot be saved to a virtual Keystore

JPS-00653
Cannot save a virtual keystore

Category:
Compliance

Cause:
Saving a virtual Keystore failed

Action:
A virtual keystore cannot be persisted

JPS-00654
Cannot delete a virtual keystore that does not exist

Category:
Compliance

Cause:
Deleting a virtual Keystore failed

Action:
Cannot delete a virtual keystore that does not exist

JPS-01000
The credential map {0} is invalid.

Category:
Requests/Responses

Cause:
The specified credential map name was invalid.

Action:
Ensure the credential map name is valid.

JPS-01001
The credential key {0} is invalid.

Category:
Requests/Responses

Cause:
The specified credential key name was invalid.

Action:
Ensure the credential key name is valid.

JPS-01002
The value {0} is invalid in this password credential.

Category:
Requests/Responses

Cause:
The specified password credential was invalid.

Action:
Use only a supported credential type. The supported types are {0}.

JPS-01003
The value of name {0}, url {1}, of port {2} is invalid in this datasource credential.

Category:
Requests/Responses

Cause:
The specified datasource credential was invalid.

Action:
Use only a supported credential type. The supported types are {0}.

JPS-01004
The value {0} is invalid in this generic credential.

Category:
Requests/Responses

Cause:
The specified generic credential was invalid.

Action:
Use only a supported credential type. The supported types are {0}.

JPS-01005
The credential type {0} is not supported.

Category:
Requests/Responses

Cause:
The specified credential type was invalid.

Action:
Use only a supported credential type. The supported types are {0}.

JPS-01006
The credential expired on {0}.

Category:
Requests/Responses

Cause:
This credential expired on {0}.

Action:
Create a new credential.

JPS-01007
The credential with map {0} and key {1} already exists.

Category:
Requests/Responses

Cause:
This credential already existed.

Action:
Use a credential with different map name or key.

JPS-01008
The credential map name {0} already exists.

Category:
Requests/Responses

Cause:
This credential map name already existed.

Action:
Use a different map name.

JPS-01009
The credential with map {0} and key {1} does not exist.

Category:
Requests/Responses

Cause:
This credential did not exist.

Action:
Check the credential map name and key.

JPS-01010
The credential map {0} does not exist.

Category:
Requests/Responses

Cause:
This credential map name did not exist.

Action:
Check the credential map name.

JPS-01011
The credential store location property {0} is not configured, or the configured value {1} is invalid.

Category:
Configuration

Cause:
The credential store location was not specified.

Action:
Check the value of the location attribute.

JPS-01012
The credential property {0} is invalid or not defined.

Category:
Requests/Responses

Cause:
The credential property {0} was invalid or not defined.

Action:
Check the configuration of this property.

JPS-01013
The credential store DN {0} is missing in the store; the target DN must be pre-configured.

Category:
Requests/Responses

Cause:
The expected credential store DN {0} was missing.

Action:
Configure this DN during the bootstrap process.

JPS-01014
The credential {0} is invalid.

Category:
Requests/Responses

Cause:
This credential was invalid.

Action:
Use only a supported credential type. The supported types are password or generic.

JPS-01015
Cannot retrieve credential {0}.

Category:
Requests/Responses

Cause:
This credential was invalid.

Action:
Use only a supported credential type. The supported types are password or generic.

JPS-01016
A password credential is expected; instead found {0} for alias {1} and key {2} at location {3}.

Category:
Other

Cause:
Wrong credential type was found.

Action:
Use the password credential type. Expecting password credential but found {0} for alias {1} and key {2} at location {3}.

JPS-01017
A generic credential is expected; instead found {0}.

Category:
Other

Cause:
Wrong credential type was found.

Action:
Use the generic credential type. Expecting generic credential but found {0}.

JPS-01018
A password credential is missing in the credential store.

Category:
Session

Cause:
The password credential was not found in the credential store.

Action:
Ensure that the credential is present in the credential store.

JPS-01019
The credential store {0} has been moved or deleted.

Category:
Configuration

Cause:
The specified credential store did not exist.

Action:
Ensure that the credential store location is valid.

JPS-01020
Cannot create store {0}.

Category:
Configuration

Cause:
Could not create the credential store.

Action:
Verify the store location, that sufficient permissions are in place, and that sufficient disk space is available.

JPS-01021
The generic credential {0} is not serializable.

Category:
Requests/Responses

Cause:
This generic credential was not serializable.

Action:
Make this credential serializable.

JPS-01022
The expiration time {0} is invalid: the expiration time must be later than the creation time.

Category:
Requests/Responses

Cause:
Invalid credential expiration time.

Action:
Set the expiration time to a time later than the credential creation time.

JPS-01023
Store does not contain all expected maps. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01024
Store contains all expected maps. Result {0}.

Category:
Compliance

Cause:

Action:

JPS-01025
Store does not contain all expected credentials. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01026
Store contains all expected credentials. Result {0}.

Category:
Compliance

Cause:

Action:

JPS-01027
Cannot get credential map. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01028
successful getting of credential map

Category:
Compliance

Cause:

Action:

JPS-01029
successful getting of credential

Category:
Compliance

Cause:

Action:

JPS-01030
Cannot get credential. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01031
Cannot retrieve map names. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01032
successful setting of credential

Category:
Compliance

Cause:

Action:

JPS-01033
Cannot set credential. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01034
successful resetting of credential

Category:
Compliance

Cause:

Action:

JPS-01035
Cannot reset credential. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01036
successful setting of credential map

Category:
Compliance

Cause:

Action:

JPS-01037
Cannot set credential map. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01038
successful resetting of credential map

Category:
Compliance

Cause:

Action:

JPS-01039
Cannot reset credential map. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01040
successful deletion of credential

Category:
Compliance

Cause:

Action:

JPS-01041
Cannot delete credential. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01042
successful deletion of credential map

Category:
Compliance

Cause:

Action:

JPS-01043
Cannot delete credential map. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01044
successful deletion of all credentials from the store

Category:
Compliance

Cause:

Action:

JPS-01045
Cannot delete all credentials from the store. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01046
successful retrieving of map names; mapNameSet {0}.

Category:
Compliance

Cause:

Action:

JPS-01047
Cannot persist the wallet. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01048
Modifying of credential failed. Reason {0}

Category:
Compliance

Cause:
Modification of credential failed

Action:
Contact system administrator

JPS-01049
Reading all credentials from the store failed. Reason {0}

Category:
Compliance

Cause:
Read of all credentials failed

Action:
Contact system administrator

JPS-01050
Opening of wallet based credential store failed. Reason {0}

Category:
Compliance

Cause:
Credential wallet could not be opened

Action:
Contact system administrator

JPS-01051
Credential audit events cannot be logged. Reason {0}

Category:
Compliance

Cause:
Credential store audit events logging not enabled

Action:
Check the audit configuration to ensure auditing enabled

JPS-01052
Credential audit event logging failed. Reason {0}

Category:
Compliance

Cause:
Credential audit event logging failed

Action:
Contact system administrator

JPS-01053
Creation of new credential map failed. Reason {0}

Category:
Compliance

Cause:
Creation of new credential map failed

Action:
Ensure all jps libraries are in setup properly in the runtime

JPS-01054
Refresh of credential wallet failed. Reason {0}

Category:
Compliance

Cause:
Refresh of credstore wallet failed

Action:
Contact system administrator

JPS-01055
Could not create credential store instance. Reason {0}

Category:
Compliance

Cause:
Could not create credential store instance

Action:
Contact system administrator

JPS-01056
The credential store location {0} was invalid. It should be a directory or full path to cwallet.sso file.

Category:
Configuration

Cause:
The credential store location {0} was invalid. It should be a directory or full path to cwallet.sso file.

Action:
Check the value of the location property

JPS-01057
The credential map was invalid. Reason {0}

Category:
Requests/Responses

Cause:
The credential map was null.

Action:
Check the value of the credential map

JPS-01058
The credential dn {0} was invalid.

Category:
Requests/Responses

Cause:
The credential dn was invalid.

Action:
Ensure the credential dn is valid.

JPS-01059
The credential store instance {0} was not fully initialized.

Category:
Configuration

Cause:
The credential store was not fully initialized until data source is available.

Action:
Wait and retry later

JPS-01060
The credential store instance does not have the property ldap url/JDBC url/datasource JNDI name defined.

Category:
Configuration

Cause:
The credential store property ldap.url or jdbc.url or datasource.jndi.name was not defined.

Action:
Check the configuration for this property.

JPS-01061
Access to boostrap credential store denied to application code.

Category:
Security

Cause:
Application code was trying to access a bootstrap credential store. Bootstrap credential store is intended only for the OPSS usage.

Action:
bootstrap_credstore_context need not be used for credential store operations.

JPS-01062
A backup of the bootstrap credential store could not be created.

Category:
Security

Cause:
A backup of the bootstrap cwallet.sso could not be created.

Action:
Investigate the logs to find out the root cause of the exception in file operations

JPS-01063
Credential compatibility check failed. Cannot migrate credential: {0}

Category:
Security

Cause:
There exists one or more generic credential in the store that cannot be migrated.

Action:
Ensure that the store does not contain any generic credential with binary attribute before migration.

JPS-01064
Invalid password: Passwords must have a minimum length of eight characters and contain alphabetic characters combined with numbers or special characters.

Category:
Security

Cause:

Action:

JPS-01065
Could not decrypt a random credential

Category:
Security

Cause:
Decryption of credential failed

Action:
Ensure that the bootstrap wallet contains the correct encryption key that was used to encrypt the credentials in the store.

JPS-01066
Cannot get credential due to database disconnected. Reason {0}.

Category:
Compliance

Cause:

Action:

JPS-01067
Failed to retrieve customer encryption key password.

Category:
Security

Cause:
No password was specified in the custom callback.

Action:
Ensure that the password for decrypting customer encryption key is provided.

JPS-01068
Missing callback handler to provide context information

Category:
Security

Cause:
No custom callback to provide context information specified.

Action:
Ensure that a callback handler is specified.

JPS-01500
The anonymous service configuration is missing.

Category:
Configuration

Cause:
The anonymous service configuration was missing in jps-config.xml.

Action:
Configure the anonymous service in jps-config.xml.

JPS-01501
The anonymous identity store provider instance {0} is not found.

Category:
Configuration

Cause:
The anonymous identity store provider configuration was invalid.

Action:
Check the anonymous identity store provider configuration in jps-config.xml.

JPS-01502
The LDAP identity store provider instance {0} is not found.

Category:
Configuration

Cause:
Invalid or missing LDAP identity store provider configuration.

Action:
Check LDAP identity store provider configuration in jps-config.xml.

JPS-01503
The XML identity store provider instance {0} is not found.

Category:
Requests/Responses

Cause:
Invalid or missing XML identity store provider configuration.

Action:
Check the XML identity store provider configuration in jps-config.xml.

JPS-01504
The secret store provider for provider {0} and instance {1} does not exist.

Category:
Requests/Responses

Cause:
The credential provider was missing.

Action:
Check the configuration of the credential store provider in jps-config.xml.

JPS-01505
The key store provider {0} is missing or not configured.

Category:
Configuration

Cause:
The keystore provider configuration was missing in jps-config.xml.

Action:
Configure a keystore provider in jps-config.xml.

JPS-01506
Invalid context name.

Category:
Configuration

Cause:
Invalid context name found.

Action:
Check the configurations of contexts in jps-config.xml.

JPS-01507
Invalid login module name.

Category:
Configuration

Cause:
Invalid login module name found.

Action:
Check the login module configurations in jps-config.xml.

JPS-01508
Invalid login module descriptor.

Category:
Configuration

Cause:
Invalid login module descriptor found.

Action:
Check the login module instance configurations in jps-config.xml.

JPS-01509
Invalid login module class name.

Category:
Configuration

Cause:
Invalid login module class name found.

Action:
Check the loginModuleClassName property in the login module instance configuration in jps-config.xml.

JPS-01510
Invalid login module entries.

Category:
Configuration

Cause:
Invalid login module entries found.

Action:
The expected login module to be invoked is not present or misconfigured. Check the login module instance configurations in jps-config.xml.

JPS-01511
Invalid login module entry.

Category:
Configuration

Cause:
The login module entries were not valid in the jps-config.xml file.

Action:
Correct the login module entries in service instances and service providers.

JPS-01512
Missing login module entry.

Category:
Configuration

Cause:
The login module entries were missing in the jps-config.xml file.

Action:
Add the appropriate login module entries in service instances and service providers.

JPS-01513
The configuration of the JAAS login provider {0} and the service instance {1} are missing.

Category:
Configuration

Cause:
The login module provider was missing.

Action:
Ensure that a login module provider is configured in the jps-config.xml.

JPS-01514
The default context is missing in jps-config.xml.

Category:
Configuration

Cause:
Default context was missing in jps-config.xml.

Action:
Add a default context to jps-config.xml.

JPS-01515
A context named anonymous is missing in jps-config.xml.

Category:
Configuration

Cause:
Context named anonymous was missing in jps-config.xml.

Action:
Add a context named anonymous in jps-config.xml file with an anonymous service instance reference.

JPS-01516
The default credential store service is missing in default jps-config.xml.

Category:
Other

Cause:
The default credential store service was missing in the default context in jps-config.xml.

Action:
There must be at least one credential store service configured in the default context.

JPS-01517
The generic identity store provider is missing.

Category:
Configuration

Cause:
Invalid or missing generic identity store provider configuration.

Action:
Check the generic identity store provider configuration in jps-config.xml.

JPS-01518
The anonymous service is not available in the application context.

Category:
Session

Cause:
The anonymous service was not available in context.

Action:
Check the context in jps-config.xml.

JPS-01519
The default context configuration is missing in jps-config.xml.

Category:
Session

Cause:
The default context configuration was not available in jps-config.xml.

Action:
Ensure that the default context is present in jps-config.xml.

JPS-01520
Cannot initialize identity store, cause: {0}.

Category:
Configuration

Cause:
Could not initialize identity store.

Action:
Correct the identity store configuration.

JPS-01521
Identity store file path is invalid.

Category:
Configuration

Cause:
Identity store file path was invalid or null.

Action:
Ensure that the path configured with the property ADF_IM_FILE_PATH is valid.

JPS-01522
The Jps configuration is invalid.

Category:
Configuration

Cause:
JPS configuration was null or invalid.

Action:
Verify configuration in jps-config.xml.

JPS-01523
The service instance {0} is invalid or not configured in jps-config.xml.

Category:
Configuration

Cause:
A service instance configuration was not valid.

Action:
Verify that the instance is correctly configured in jps-config.xml.

JPS-01524
The service instance {0} is invalid or not configured in jps-config.xml.

Category:
Configuration

Cause:
A service provider configuration was invalid.

Action:
Veirfy that the provider is correctly configured in jps-config.xml.

JPS-01525
The identity store service is not properly configured.

Category:
Configuration

Cause:
Found invalid identity store service configuration in jps-config.xml.

Action:
Ensure a valid identity store configuration in jps-config.xml.

JPS-01526
Configured identity store, user manager, or role manager is invalid. The error is {0}.

Category:
Configuration

Cause:
Found null value for configured identity store, user manager, or role manager.

Action:
Correct the identity store configuration.

JPS-01527
The identity store factory name is not configured.

Category:
Configuration

Cause:
Could not find identity store factory name.

Action:
Use the property ADF_IM_FACTORY_CLASS to specify the factory class.

JPS-01528
Idm identity store is invalid.

Category:
Configuration

Cause:
The identity store was not configured correctly.

Action:
Correct the configuration of the identity store in jps-config.xml.

JPS-01529
The context {0} contains multiple services of type {1}.

Category:
Configuration

Cause:
The context {0} contains multiple services of type {0}.

Action:
Check jps-config.xml for correctness.

JPS-01530
The anonymous service is already configured in the context {0}.

Category:
Configuration

Cause:
The anonymous service is already configured in the context {0}.

Action:
Check jps-config.xml for correctness.

JPS-01531
Configuration location {0} is a directory. File name expected.

Category:
Configuration

Cause:
Configuration location {0} is a directory. File name expected.

Action:
Provide a valid configuration file location, including a file name.

JPS-01532
The service instance location {0} is invalid or not configured in jps-config.xml.

Category:
Configuration

Cause:
A service instance configuration was invalid.

Action:
Verify that the location of the instance is correctly configured in jps-config.xml.

JPS-01533
Failed to create service instance {0} for application {1}.

Category:
Configuration

Cause:
Failed to create service instance {0} for application {1}.

Action:
Check the log files to resolve the error.

JPS-01534
Failed to get identity store configuration.

Category:
Security

Cause:
Failed to get identity store configuration.

Action:
Ensure the configuration is available.

JPS-01535
Failed to get configuration name {0}.

Category:
Configuration

Cause:
Failed to get configuration name {0}.

Action:
Check the log files to resolve the error.

JPS-01536
Failed to evaluate XML expression on Object {0}.

Category:
Configuration

Cause:
Failed to evaluate XML expression on Object {0}.

Action:
Check the log files to resolve the error.

JPS-01537
Failed to handle config location {0}. Reason {1}.

Category:
Security

Cause:

Action:

JPS-01538
The default policy provider was not found.

Category:
Security

Cause:
The default policy provider was not found.

Action:
Ensure policy provider configuration is correct.

JPS-01539
The Ovd IGF service provider instance {0} is not found.

Category:
Configuration

Cause:
Invalid or missing Ovd IGF service provider configuration.

Action:
Check Ovd IGF service provider configuration in jps-config.xml.

JPS-01543
The value of {0} is invalid. It must be an integer.

Category:
Configuration

Cause:
attribute.expire.time.seconds is not an integer.

Action:
Ensure attribute.expire.time.seconds is a valid integer.

JPS-01544
The provided configuration file path {0} is invalid or null.

Category:
Configuration

Cause:
The provided configuration file path {0} is invalid or null.

Action:
Provide a valid configuration file path.

JPS-01545
Back up of JPS Config file {0} done.

Category:
Configuration

Cause:
Back up of JPS Config file {0} done.

Action:
No action required

JPS-02000
The authentication of user {0} succeeded.

Category:
Requests/Responses

Cause:

Action:

JPS-02001
The authentication of user {0} failed. Reason: {1}

Category:
Requests/Responses

Cause:
User authentication failed.

Action:
Ensure the user exists in the identity store. Check the user credentials that are being sent for authentication.

JPS-02003
Authentication failed.

Category:
Requests/Responses

Cause:
Could not authenticate user.

Action:
Ensure that authentication uses valid user name and password.

JPS-02004
Cannot authenticate user {0}.

Category:
Security

Cause:
Could not authenticate user.

Action:
Ensure that the credentials provided for authentication are correct.

JPS-02005
Cannot login user {0} because {1}. Check the log files for more details.

Category:
Requests/Responses

Cause:
Encountered an error while authenticating user.

Action:
Contact the domain administrator.

JPS-02008
Authenticated role name is invalid: property {0} is invalid or not configured.

Category:
Configuration

Cause:
Found invalid or undefined authentication role name property.

Action:
Ensure that authentication role name properties are valid in jps-config.xml.

JPS-02009
SAML trusted assertion issuer is not configured: property set {0} is not configured.

Category:
Configuration

Cause:
Could not find configuration for SAML trusted assertion issuer.

Action:
Set the property saml.trusted.issuers in jps-config.xml.

JPS-02010
Cannot verify SAML assertion.

Category:
Requests/Responses

Cause:
Found invalid assertion; SAML trusted assertion issuer was not configured.

Action:
Check assertion and set the property saml.trusted.issuers in jps-config.xml.

JPS-02011
SAML assertion is missing name identifier.

Category:
Requests/Responses

Cause:
Found invalid assertion: name identifier was missing.

Action:
Ensure the use of a valid assertion.

JPS-02012
SAML assertion subject name is invalid.

Category:
Requests/Responses

Cause:
Found invalid assertion: subject name was null.

Action:
Ensure the use of a valid assertion.

JPS-02013
SAML assertion issuer name is invalid.

Category:
Requests/Responses

Cause:
Found invalid assertion: issuer name was invalid.

Action:
Ensure the use of a valid assertion.

JPS-02014
SAML assertion is invalid.

Category:
Requests/Responses

Cause:
Found invalid assertion.

Action:
Ensure the use of a valid assertion.

JPS-02015
SAML assertion has missing subject.

Category:
Requests/Responses

Cause:
Found invalid assertion: subject statement was missing.

Action:
Ensure the use of a valid assertion.

JPS-02016
SAML assertion is missing conditions.

Category:
Requests/Responses

Cause:
Found invalid assertion: condition statement was missing.

Action:
Ensure the use of a valid assertion.

JPS-02017
Found invalid condition "not before" in SAML assertion. Current Time:{0}, {1} milli seconds, {2} Time:{3}.

Category:
Requests/Responses

Cause:
Found invalid condition "not before" in SAML assertion. Current Time:{0}, {1} milli seconds, {2} Time:{3}.

Action:
Verify that the condition "not before" in the SAML assertion is set to a date earlier than or equal to today's date.

JPS-02018
Found invalid condition "on or after" in SAML assertion. Current Time:{0}, {1} milli seconds, {2} Time:{3}.

Category:
Requests/Responses

Cause:
Found invalid condition "on or after" in SAML assertion. Current Time:{0}, {1} milli seconds, {2} Time:{3}.

Action:
Verify that the condition "on or after" in the SAML assertion is set to a valid date.

JPS-02019
SAML assertion is missing assertion issuers signature.

Category:
Requests/Responses

Cause:
Found invalid assertion: assertion issuers signature was missing.

Action:
Ensure the use of a valid assertion.

JPS-02020
Signature for SAML assertion issuer is invalid.

Category:
Configuration

Cause:
Found invalid signature in SAML assertion issuer.

Action:
Ensure the use of a valid assertion.

JPS-02021
Signature certificate (X509 Data) for SAML assertion issuer is invalid.

Category:
Configuration

Cause:
Found invalid signature certificate (X509 Data) in SAML assertion.

Action:
Ensure the use of a valid assertion.

JPS-02022
Cannot verify signature for SAML assertion.

Category:
Configuration

Cause:
Failed to verify issuers signature in assertion.

Action:
Check the assertion and set the property saml.trusted.issuers in jps-config.xml.

JPS-02023
Cannot verify SAML assertion signature certificate path.

Category:
Configuration

Cause:
Found invalid assertion signature.

Action:
Check the assertion and set the property saml.trusted.issuers in jps-config.xml.

JPS-02024
Cannot retrieve trusted CA policy for issuer {0}.

Category:
Configuration

Cause:
Found invalid assertion.

Action:
Check the assertion and set the property saml.trusted.issuers in jps-config.xml.

JPS-02025
Cannot modify read-only Subject.

Category:
Requests/Responses

Cause:
Could not modify a read-only subject.

Action:
Ensure the program logic is correct and that the program does not attempt to modify a read-only subject.

JPS-02026
X509 certificate is invalid.

Category:
Other

Cause:
The X509 certificate passed to the callback handler was null or invalid.

Action:
Ensure that the callback handler uses a valid X509 certificate.

JPS-02027
The property set {0} is missing in jps-config.xml.

Category:
Configuration

Cause:
Could not find property set in jps-config.xml.

Action:
Configure the property set in jps-config.xml.

JPS-02028
The extended property set {0} is missing in jps-config.xml.

Category:
Configuration

Cause:
Could not find extended property set in jps-config.xml.

Action:
Configure the extended property set in jps-config.xml.

JPS-02029
The default realm is not configured in identity store service {0}.

Category:
Configuration

Cause:
Could not find the default realm in the identity store service.

Action:
Configure the default realm property in the identity store service.

JPS-02030
The default realm configured in identity store service {0} is empty or null.

Category:
Configuration

Cause:
Found null default realm configured in identity store service.

Action:
Configure the default realm property in the identity store service.

JPS-02031
The invalid realm name property {0} is configured in identity store service {1}.

Category:
Configuration

Cause:
Found invalid realm name property in identity store service.

Action:
Configure the correct realm name property in the identity store service.

JPS-02032
The duplicate realm name {0} is configured in identity store service {1}.

Category:
Configuration

Cause:
Found duplicate realm in identity store service.

Action:
Remove duplicate realm configuration from the identity store service.

JPS-02033
The realm name {0} passed for authentication is invalid. Was expecting {1}, but found {0}.

Category:
Configuration

Cause:
Found invalid realm name {0}. Was expecting {1}, but found {0}.

Action:
Check the realm name passed to the authentication of user name.

JPS-02034
Realm name is missing in user name for authentication in multi-realm configuration.

Category:
Configuration

Cause:
The realm name was not supplied for authentication of multi-realm configuration.

Action:
Ensure that the realm name value is passed in the user name when authenticating a multi-realm configuration.

JPS-02035
Cannot properly initialize the Kerberos authenticator.

Category:
Requests/Responses

Cause:
Could not initialize the Kerberos authenticator.

Action:
Check the log files for errors and contact the domain administrator.

JPS-02036
Browser does not support Kerberos authentication.

Category:
Requests/Responses

Cause:
Could not find support for Kerberos authentication, or it was not configured correctly.

Action:
Verify that the browser is set to allow Kerberos authentication.

JPS-02037
The SAML assertion issuer {0} certificate is missing from the keystore.

Category:
Configuration

Cause:
Could not find SAML assertion certificate in keystore.

Action:
Store the SAML assertion issuer's certificate in the keystore, and configure the trustpoint alias in JpsSAMLLoginModuule.

JPS-02038
The SAML assertion {0} is missing a signature.

Category:
Requests/Responses

Cause:
Could not find expected signature in assertion.

Action:
Check that the assertion sent has a valid signature.

JPS-02039
Cannot assert certificate. Reason {0}.

Category:
Requests/Responses

Cause:
Found invalid certificate, or could not find corresponding user in identity store.

Action:
Make sure that the assertion is valid.

JPS-02040
Both user identity and token were provided for assertion. Either user identity or token should be provided, not both.

Category:
Other

Cause:
Both user identity and token were provided for assertion.

Action:
Provide either user identity or a token for assertion, not both.

JPS-02041
Asserter class was configured as {0}, but does not implement {1}.

Category:
Other

Cause:
Assertor class was configured as {0}, but does not implement {1}.

Action:
Provide an Assertor that implements {1}.

JPS-02042
Token assertion failed.

Category:
Other

Cause:
Token assertion failed.

Action:
Check detailed logs for more information.

JPS-02043
User name cannot be null or empty.

Category:
Requests/Responses

Cause:
User name cannot be null or empty.

Action:
Check that the user name is not null or empty.

JPS-02044
Found invalid attesting entity in SAML assertion. Attesting entity: {0}.

Category:
Requests/Responses

Cause:
Found invalid attesting entity in SAML assertion. Attesting entity: {0}.

Action:
Check that the attesting entity for the SAML assertion is valid.

JPS-02045
Audience URI for SAML assertion is invalid.

Category:
Requests/Responses

Cause:
SAML assertion audience URI is invalid.

Action:
Check that the audience URI for the SAML assertion is valid.

JPS-02046
Cannot get the user name from SAML assertion name identifier: {0}.

Category:
Requests/Responses

Cause:
Cannot get the user name from SAML assertion name identifier: {0}.

Action:
Check that the name identifier for the SAML assertion is valid.

JPS-02047
SAMLNameIdentifierMapper class was configured as {0}, but does not implement oracle.security.jps.internal.jaas.module.saml.SAMLNameIdentifierMapper.

Category:
Other

Cause:
SAMLNameIdentifierMapper class was configured as {0}, but does not implement oracle.security.jps.internal.jaas.module.saml.SAMLNameIdentifierMapper.

Action:
Provide an SAMLNameIdentifierMapper that implements oracle.security.jps.internal.jaas.module.saml.SAMLNameIdentifierMapper.

JPS-02048
Incorrect password was provided.

Category:
Requests/Responses

Cause:
Incorrect password was provided.

Action:
Ensure that authentication uses correct password.

JPS-02049
Null or empty password was provided.

Category:
Requests/Responses

Cause:
Null or empty password was provided.

Action:
Ensure that authentication uses correct password.

JPS-02050
Signature verification failed. Principal: {0}

Category:
Security

Cause:
Signature verification failed.

Action:
This error is unlikely to occur. Contact technical support when necessary.

JPS-02051
No auth module to validate request: auth context ID "{0}" of application context "{1}".

Category:
Security

Cause:
Server auth context did not have auth module to validate request.

Action:
Ensure that the server auth module is properly configured and bound for use by applications.

JPS-02052
No auth module to secure response: auth context ID "{0}" of application context "{1}".

Category:
Security

Cause:
Server auth context did not have auth module to secure response.

Action:
Ensure that the server auth module is properly configured and bound for use by applications.

JPS-02053
No auth module to validate response: auth context ID "{0}" of application context "{1}".

Category:
Security

Cause:
Client auth context did not have auth module to validate response.

Action:
Ensure that the client auth module is properly configured and bound for use by applications.

JPS-02054
No auth module to secure request: auth context ID "{0}" of application context "{1}".

Category:
Security

Cause:
Client auth context did not have auth module to secure request.

Action:
Ensure that the client auth module is properly configured and bound for use by applications.

JPS-02055
Cannot instantiate auth module class "{0}" for application context "{1}", cause: {2}.

Category:
Security

Cause:
Could not load the auth module.

Action:
Ensure that the module class name is correctly supplied and the class is in the class path.

JPS-02056
The auth module must support message type: {0}.

Category:
Security

Cause:
Auth module did not support the required message type.

Action:
Ensure that the class correctly implements the required auth module interfaces.

JPS-02057
The message layer "{0}" is not supported.

Category:
Requests/Responses

Cause:
The specified message layer was not supported.

Action:
Provide a valid message layer.

JPS-02058
Null callback handler is not supported.

Category:
Requests/Responses

Cause:
The specified callback handler was null.

Action:
Supply a non-null callback handler.

JPS-02059
The default auth provider "{0}" for layer "{1}" is not configured.

Category:
Configuration

Cause:
The default auth provider was not configured.

Action:
Ensure that the provider is configured in jps-config.xml.

JPS-02060
The auth module "{0}" is missing.

Category:
Configuration

Cause:
The specified auth module did not exist.

Action:
Configure the auth module in jps-config.xml.

JPS-02061
No auth module configured for provider "{0}".

Category:
Configuration

Cause:
No auth module configured for the specified provider.

Action:
Configure an auth module for the provider in jps-config.xml.

JPS-02062
Cannot determine the JDK vendor. Defaults to Oracle JDK Kerberos Login Module.

Category:
Configuration

Cause:
Cannot determine the JDK vendor. Defaults to Oracle JDK Kerberos Login Module.

Action:
See error message.

JPS-02063
Failed to create Kerberos Login Module instance "{0}". Reason: {1}.

Category:
Requests/Responses

Cause:
Failed to create Kerberos Login Module instance "{0}". Reason: {1}.

Action:
Ensure that the Login Module class name is correctly supplied and the class is in the class path.

JPS-02064
Cannot retrieve value for key {0}. Expecting key type {1}, found {2}.

Category:
Configuration

Cause:
Found invalid object type in role mapping map for key {0}. Expecting {1}, Found {2}.

Action:
Check the role mapping values passed in the callback.

JPS-02066
Cannot map default service role

Category:
Configuration

Cause:
default service roles are missing in the role mapping provided.

Action:
Check the role mapping values passed in the callback. Default service role should be provided if mapping of roles is enabled but mapping is not provided

JPS-02500
The principal name is invalid.

Category:
Requests/Responses

Cause:
Found null principal name.

Action:
Check the principal name.

JPS-02501
The principal type {0} is invalid.

Category:
Requests/Responses

Cause:
Found invalid principal type.

Action:
Check the principal type.

JPS-02502
The password {0} is invalid.

Category:
Data

Cause:
Found invalid password.

Action:
Check the password passed to create user account.

JPS-02503
The user name {0} is invalid.

Category:
Data

Cause:
Found invalid user name.

Action:
Ensure that the user name used to create, fetch, or remove the account is valid.

JPS-02504
The user range starting at {0} and ending at {1} is not a valid range.

Category:
Data

Cause:
The user range was invalid.

Action:
Check the start and end range. The start range cannot be less than 0, and the end range cannot be less than start range.

JPS-02505
The group {0} is invalid.

Category:
Data

Cause:
Group name was invalid.

Action:
Check the group name that is being sent for creating/fetching/removing group.

JPS-02506
The group range starting at {0} and ending at {1} is not valid range.

Category:
Data

Cause:
The JPSUserManager.getGroups() method was invoked with invalid start or end range.

Action:
Check the start and end range. The start range cannot be less than 0, and the end range cannot be less than start range.

JPS-02507
The anonymous user is not found.

Category:
Session

Cause:
The anonymous user was not found.

Action:
Ensure that a valid anonymous user is configured.

JPS-02508
The anonymous user name is invalid; property {0} is invalid or not defined.

Category:
Configuration

Cause:
The anonymous.user.name property was not configured in the anonymous service configuration.

Action:
Configure the anonymous.user.name property to a valid user name in the identity store while configuring the Anonymous Service.

JPS-02509
The user {0} already exists in the store; choose a different user name.

Category:
Requests/Responses

Cause:
The specified user name already existed in the store.

Action:
Provide a different user name.

JPS-02510
The group {0} already exists in the store; choose a different group name.

Category:
Requests/Responses

Cause:
The specified group name already existed in the store.

Action:
Provide a different group name.

JPS-02511
The role for group {0} is invalid.

Category:
Requests/Responses

Cause:
Found null role in group.

Action:
Check the group's name.

JPS-02512
Cannot create a new user {0}.

Category:
Configuration

Cause:
Could not create user.

Action:
Ensure that the user name is valid and distinct from any other existing user name.

JPS-02513
Cannot drop user {0}.

Category:
Configuration

Cause:
Could not drop the user.

Action:
Ensure this user already exists.

JPS-02514
Cannot retrieve user profile.

Category:
Configuration

Cause:
Could not get profile for user.

Action:
Ensure that the user exists.

JPS-02515
Cannot update user profile.

Category:
Configuration

Cause:
Could not set profile for user.

Action:
Ensure that the user exists.

JPS-02516
Cannot retrieve role profile.

Category:
Configuration

Cause:
Could not get role profile.

Action:
Ensure that the role exists.

JPS-02517
Cannot update role profile.

Category:
Configuration

Cause:
Could not set role profile.

Action:
Ensure that the role exists.

JPS-02518
Cannot create role {0}.

Category:
Security

Cause:
Could not create role.

Action:
Ensure that the role exists.

JPS-02519
Cannot drop role {0}.

Category:
Configuration

Cause:
Could not drop role.

Action:
Ensure that the role exists.

JPS-02520
Cannot grant role to the principal.

Category:
Configuration

Cause:
Could not grant permission to role.

Action:
Ensure that the permission is set for the role.

JPS-02521
Cannot revoke role from principal.

Category:
Configuration

Cause:
Could not revoke role.

Action:
Check that the correct permission to revoke the role is set.

JPS-02522
Cannot add user to role owners.

Category:
Configuration

Cause:
Could not add owner to role.

Action:
Check log files and correct the appropriate configuration.

JPS-02523
Cannot remove user from role owners.

Category:
Configuration

Cause:
Could not remove owner from role.

Action:
Check log files and correct the appropriate configuration.

JPS-02524
Cannot retrieve role owners.

Category:
Configuration

Cause:
Could not get role owners.

Action:
Check log files and correct the appropriate configuration.

JPS-02525
Cannot retrieve role grantees.

Category:
Configuration

Cause:
Could not get role grantees.

Action:
Check log files and correct the appropriate configuration.

JPS-02526
Cannot retrieve the roles granted to principal.

Category:
Configuration

Cause:
Could not get granted roles.

Action:
Check log files and correct the appropriate configuration.

JPS-02527
Cannot close identity store.

Category:
Configuration

Cause:
Could not close identity store.

Action:
Check log files and correct the appropriate configuration.

JPS-02528
Cannot obtain a handle for role manager MBean.

Category:
Configuration

Cause:
Could not get role manager object name.

Action:
Check log files and correct the appropriate configuration.

JPS-02529
Cannot obtain a handle for user manager MBean.

Category:
Configuration

Cause:
Could not get user manager object name.

Action:
Check log files and correct the appropriate configuration.

JPS-02530
Cannot get a list of searchable attributes.

Category:
Configuration

Cause:
Could not get searchable attributes.

Action:
Check log files and correct the appropriate configuration.

JPS-02531
Cannot get list of user property names.

Category:
Configuration

Cause:
Could not get user property names.

Action:
Check log files and correct the appropriate configuration.

JPS-02532
Cannot parse principals of role.

Category:
Configuration

Cause:
Could not parse role principals.

Action:
Check log files and correct the appropriate configuration.

JPS-02533
Cannot parse principals of user.

Category:
Configuration

Cause:
Could not parse user principals.

Action:
Check log files and correct the appropriate configuration.

JPS-02534
Cannot find role {0}.

Category:
Configuration

Cause:
Could not completer search role operation.

Action:
Correct the role name and, if necessary, contact the domain administrator.

JPS-02535
Cannot complete search for roles.

Category:
Configuration

Cause:
Could not complete search for multiple roles.

Action:
Correct role names and, if necessary, contact the domain administrator.

JPS-02536
Cannot complete search for user {0}.

Category:
Configuration

Cause:
Could not completer user search.

Action:
Correct user name and, if necessary, contact the domain administrator.

JPS-02537
Cannot complete search for users.

Category:
Configuration

Cause:
Could not complete search for multiple users.

Action:
Correct user names and, if necessary, contact the domain administrator.

JPS-02538
Cannot complete search operation.

Category:
Configuration

Cause:
Failed to complete search.

Action:
Correct the search query.

JPS-02539
Cannot change password of user {0}.

Category:
Configuration

Cause:
Could not change password.

Action:
Contact the domain administrator.

JPS-02540
User {0} not found in the identity store.

Category:
Configuration

Cause:
User {0} not found in the identity store.

Action:
Ensure user is valid.

JPS-02541
Identity store has an invalid configured subscriber name.

Category:
Configuration

Cause:
Found invalid subscriber name.

Action:
Correct the configuration of property subscriber.name.

JPS-02542
unknown identity store service type {0}.

Category:
Configuration

Cause:
Found unknown identity store service type {0}.

Action:
Correct the identity store configuration.

JPS-02543
Search type {0} is invalid.

Category:
Other

Cause:
Found invalid search type {0}.

Action:
Correct the type passed for the search.

JPS-02544
Operation type {0} is invalid.

Category:
Other

Cause:
Found invalid operation type {0}.

Action:
Correct the type passed for the operation.

JPS-02545
Search filter type {0} is invalid.

Category:
Other

Cause:
Found invalid search filter type {0}.

Action:
Correct the type passed for the search filter.

JPS-02546
Scope type is invalid {0}.

Category:
Other

Cause:
Found invalid scope type {0}.

Action:
Correct the type passed for the scope.

JPS-02547
Cannot create realm {0}.

Category:
Requests/Responses

Cause:
Could not created realm.

Action:
Check log files for error details.

JPS-02548
Cannot delete realm {0}.

Category:
Requests/Responses

Cause:
Could not delete realm.

Action:
Check log files for error details.

JPS-02549
A realm with the specified name already exists.

Category:
Requests/Responses

Cause:
A realm with the specified name already exists.

Action:
Choose a different realm name.

JPS-02550
The realm {0} does not exist.

Category:
Requests/Responses

Cause:
Could not find realm with the name {0}.

Action:
Correct the supplied realm name.

JPS-02551
Cannot perform an unsupported operation on a serialized object.

Category:
Requests/Responses

Cause:
Could not perform operation on serialized object.

Action:
Check log files for error details.

JPS-02552
Cannot add a duplicate owner.

Category:
Data

Cause:
Attempted to add already present owner.

Action:
Correct the owner's name.

JPS-02553
Cannot remove an owner that is not present.

Category:
Data

Cause:
Attempted to remove a non existing owner.

Action:
Correct the owner's name.

JPS-02554
Cannot add a duplicate member.

Category:
Requests/Responses

Cause:
Attempted to add already present member.

Action:
Correct the member's name.

JPS-02555
Cannot complete identity store operation. The error is {0}.

Category:
Requests/Responses

Cause:
Could not perform identity store operation.

Action:
Check error log files for details.

JPS-02556
Run into error {0} while using identity store.

Category:
Requests/Responses

Cause:
Run into an internal identity store error.

Action:
Check error log files for details.

JPS-02557
The group {0} is invalid.

Category:
Requests/Responses

Cause:
Found null or invalid group.

Action:
Correct the group's name.

JPS-02558
Operation isOwnedBy failed.

Category:
Configuration

Cause:
Could not perform operation isOwnedBy.

Action:
Correct the owner's name.

JPS-02559
Operation isManagedBy failed.

Category:
Configuration

Cause:
Could not perform operation isManagedBy.

Action:
Correct the name.

JPS-02560
Cannot update role.

Category:
Configuration

Cause:
Could not update role.

Action:
Verify that the role name is correct and, if necessary, contact the domain administrator.

JPS-02561
The realm entry {0} is missing in the identity store XML file.

Category:
Configuration

Cause:
Could not find realm entry {0} in XML-based identity store.

Action:
Ensure that the realm name is present in the XML-based identity store.

JPS-02562
Identity store entry is missing in the identity store XML file.

Category:
Configuration

Cause:
Could not find identity store entry in XML-based identity store.

Action:
Ensure that entry is present in the XML-based identity store.

JPS-02563
Length of the name attribute should be more than {0}.

Category:
Configuration

Cause:
Found attribute name with less than {0} characters.

Action:
Ensure that the length of the attribute name is at least the minimum length.

JPS-02564
Length of the name attribute should be less than {0}.

Category:
Configuration

Cause:
Found attribute name with more than {0} characters.

Action:
Ensure that the length of the attribute name is at most the maximum length.

JPS-02565
Name attribute contains invalid characters.

Category:
Configuration

Cause:
Found invalid characters in attribute name.

Action:
Ensure that attribute names have characters in the following sets only: [a-z], [A-Z], [0-9], ['.', '-', '_'].

JPS-02566
The identity store config property {0} with value {1} is invalid.

Category:
Configuration

Cause:
Found invalid identity store configuration property.

Action:
Correct the configuration of the identity store property.

JPS-02567
The credential with map {0} and key {1} does not exist.

Category:
Configuration

Cause:
Could not find credential with map and key names provided.

Action:
Ensure that a credential with given map and key is present in the credential store.

JPS-02568
The password credential with map {0} and key {1} is invalid.

Category:
Configuration

Cause:
Found invalid user name or password.

Action:
Ensure that the user name and password in the credential store are correct.

JPS-02569
Cannot find the XML file {0}.

Category:
Configuration

Cause:
Could not find XML file for XML-based identity store {0}.

Action:
Check the path of the XML file specified for the identity store.

JPS-02570
XML file is unspecified.

Category:
Configuration

Cause:
Could not determine XML file.

Action:
Specify the XML file for the XML-based repository.

JPS-02571
The algorithm {0} to encode passwords is not supported.

Category:
Configuration

Cause:
Found invalid password encoding algorithm.

Action:
Specify a valid algorithm for password encoding.

JPS-02572
Caller does not have IdentityAssertion permission to execute this operation. Reason {0}.

Category:
Requests/Responses

Cause:
Caller did not have IdentityAssertion permission.

Action:
Make sure the caller has IdentityAssertion permission to execute this operation.

JPS-02573
Cannot grant a role to itself.

Category:
Configuration

Cause:
Attempted to grant a role to itself.

Action:
Verify that no role is being granted to itself.

JPS-02574
Cannot delete default realm.

Category:
Requests/Responses

Cause:
Could not delete default realm.

Action:
The default realm cannot be deleted: assign another realm as the default realm before deleting this one.

JPS-02575
A user with the specified name does not exist.

Category:
Requests/Responses

Cause:
Could not find user with the specified name.

Action:
Check the user name.

JPS-02576
A role with the specified name already exists.

Category:
Requests/Responses

Cause:
Role with the specified name already existed.

Action:
Use a different role name.

JPS-02577
A role with the specified name does not exist.

Category:
Requests/Responses

Cause:
Could not find role with the specified name.

Action:
Check the role name.

JPS-02578
The principal type {0} is invalid for the identity store type {1}.

Category:
Requests/Responses

Cause:
Found unsupported principal type {0} for identity store type {1}.

Action:
Verify that principals have supported types.

JPS-02579
Identity store type for application {0} is null or empty.

Category:
Requests/Responses

Cause:
Found null identity store type configured in identity store.

Action:
Pass one of the following identity store types: XML, OID, ACTIVE_DIRECTORY, IPLANET, EDIRECTORY, OPEN_LDAP, COREID, OVD, OUD, or CUSTOM.

JPS-02580
Cannot grant role {0} to {1} because it would lead to a cyclic dependency.

Category:
Requests/Responses

Cause:
Could not grant role {0} to {1}, because it would lead to a cyclic dependency.

Action:
Revoke the grant which would create the cyclic dependency, and try again.

JPS-02582
LDAP user or group search base is invalid.

Category:
Requests/Responses

Cause:
Found invalid LDAP user or group search base.

Action:
Check that the user and group search base properties are valid.

JPS-02583
JPS principal "{0}" with identity store type "{1}" cannot be created.

Category:
Security

Cause:
JPS principal "{0}" with identity store type "{1}" cannot be created.

Action:
Ensure the principal value is valid.

JPS-02584
JPS user name "{0}", principal type "{1}" with identity store type "{2}" cannot be created.

Category:
Security

Cause:
JPS user name "{0}", principal type "{1}" with identity store type "{2}" cannot be created.

Action:
Ensure the user value is valid.

JPS-02585
JPS enterprise role name "{0}", principal type "{1}" with identity store type "{2}" cannot be created.

Category:
Security

Cause:
JPS enterprise role name "{0}", principal type "{1}" with identity store type "{2}" cannot be created.

Action:
Ensure the enterprise role value is valid.

JPS-02586
JPS application role name "{0}", principal type "{1}" cannot be created.

Category:
Security

Cause:
JPS application role name "{0}", principal type "{1}" cannot be created.

Action:
Ensure the application role value is valid.

JPS-02587
Principal class "{0}", name "{1}" cannot be created.

Category:
Security

Cause:
Principal class "{0}", name "{1}" cannot be created.

Action:
Ensure the principal value is valid.

JPS-02588
Enterprise user principal "{0}" cannot be created. Reason: {1}.

Category:
Security

Cause:
Enterprise user principal "{0}" cannot be created.

Action:
Ensure the user principal value is valid.

JPS-02589
Enterprise role principal "{0}" cannot be created. Reason: {1}.

Category:
Security

Cause:
Enterprise role principal "{0}" cannot be created.

Action:
Ensure the role principal value is valid.

JPS-02590
Token type {0} cannot be supported. Supported types are: {1}.

Category:
Configuration

Cause:
Token type {0} cannot be supported. Supported types are: {1}.

Action:
Use the Supported types.

JPS-02591
Guid {0} is assigned to principal {1}.

Category:
Security

Cause:
Guid {0} is assigned to principal {1}.

Action:
Check log for more details.

JPS-02592
Failed to push ldap config data to libOvd for service instance "{0}" in JPS context "{1}", cause: {2}

Category:
Security

Cause:
Failed to push ldap config data to libOvd for service instance "{0}" in JPS context "{1}", cause: {2}

Action:
Check libOvd log for more details.

JPS-02593
Failed to get IGF UserManager or RoleManager instance from IGF API, cause: {0}

Category:
Security

Cause:
Failed to get IGF UserManager or RoleManager instance from IGF API, cause: {0}

Action:
Check IGF API or libOvd log for more details.

JPS-02594
The service instance "{0}" in JPS context "{1}" has no LDAP instance configured

Category:
Security

Cause:
The service instance "{0}" in JPS context "{1}" has no LDAP instance configured

Action:
Check jps-config.xml to make sure the IGF service has either the IDStore instance defined, or use the WlsLdapIdStoreConfigProvider to get LDAP config from WLS Authentication providers.

JPS-02595
The IGFService specified ldap "{0}" is not defined in the JPS service instances

Category:
Security

Cause:
The IGFService specified ldap "{0}" is not defined in the JPS service instances

Action:
Check jps-config.xml to make sure the specified ldap is defined as a JPS service instance.

JPS-02596
The provider class type for the specified ldap instance "{0}" is configured as "{1}", which not the expected type of "oracle.security.jps.internal.idstore.ldap.LdapIdentityStoreProvider"

Category:
Security

Cause:
The provider class type for the specified ldap instance "{0}" is configured as "{1}", which not the expected type of "oracle.security.jps.internal.idstore.ldap.LdapIdentityStoreProvider"

Action:
Check jps-config.xml to make sure the provider type class for ldap instance is "oracle.security.jps.internal.idstore.ldap.LdapIdentityStoreProvider".

JPS-02597
You configured a custom Authentication Provider or WLS generic LDAPAuthenticator, which the libOvd can not recognize. Supply the idstore.type property in jps-config.xml file, or use a specific WLS LDAP Authentication provider that matches your LDAP server instead of a generic one.

Category:
Security

Cause:
You configured a custom Authentication Provider or WLS generic LDAPAuthenticator, which is a custom type and not supported by libOvd

Action:
The "idstore.type" property must be specified in jps-config.xml file as specific type such as OID, OVD etc. Alternatively, select a specific WLS LDAP Authentication provider that matches your LDAP server.

JPS-02598
Pushed ldap name and types info to libOvd. Ldaps : {0}.

Category:
Security

Cause:
libOvd is enabled so Ldap configuration info is passed to libOvd

Action:
No action required

JPS-02599
The configured Identity Store provider "{0}" is not supported by IDM IdentityDirectory

Category:
Security

Cause:
The configured Identity Store provider "{0}" is not supported by IDM IdentityDirectory

Action:
Use supported Identity Store provider for the IdentiyStoreService

JPS-02600
libOvd required system parameter of "common.components.home" is not supplied in the JVM command line

Category:
Security

Cause:
libOvd required system parameter of "common.components.home" is not supplied in the JVM command line

Action:
Supply the system flag of "-Dcommon.components.home" and point it to the oracle_common folder

JPS-02601
Failed to get Ovd virtualization service for service instance "{0}" in JPS context "{1}", cause: {2}

Category:
Security

Cause:
Failed to get Ovd virtualization service for service instance "{0}" in JPS context "{1}", cause: {2}

Action:
Check Ovd log for more details.

JPS-03000
Cannot instantiate permission class "{0}", target "{1}", or actions "{2}" as defined in the application policy context "{3}". Cause {4}

Category:
Security

Cause:
Could not load a permission class.

Action:
Ensure that the class name is correct and available in the current class loader.

JPS-03001
Cannot instantiate permission class "{0}", target "{1}", or actions "{2}" as defined in the system policy context. Cause {3}

Category:
Security

Cause:
Could not load a class.

Action:
Ensure that the class name is correct and is available in the current class loader.

JPS-03004
Cannot log check authorization event to the audit service.

Category:
Security

Cause:
Could not log check authorization events to the audit service.

Action:
Ensure that auditing is configured correctly in your environment and application.

JPS-03005
LDAP policy store contains invalid configuration parameters.

Category:
Security

Cause:
Found invalid parameters in LDAP policy store configuration.

Action:
Check the configuration of the LDAP policy store.

JPS-03006
The name "{0}" of application role "{1}" is missing or invalid.

Category:
Security

Cause:
Found missing or invalid name in application role.

Action:
The internal identifier generated by the policy store seems malformed, due to an internal policy store error; contact Oracle Support Services.

JPS-03007
Authorization check permission succeeded.

Category:
Security

Cause:

Action:

JPS-03008
Authorization check permission failed.

Category:
Security

Cause:
Current Subject or source code did not have required permissions

Action:
Provide the required permissions.

JPS-03009
Executing privileged action in {0} mode as subject {1}.

Category:
Security

Cause:

Action:

JPS-03010
Policy store cleanup thread started.

Category:
Security

Cause:

Action:

JPS-03011
Policy store cleanup thread stopped.

Category:
Security

Cause:

Action:

JPS-03012
Error occurred when computing application roles in application context {0} for subject {1}. Exception: {2}

Category:
Security

Cause:
Error occurred when computing application roles in application context {0} for subject {1}. Exception: {2}

Action:
Refer to the base exception in logs to resolve the issue.

JPS-03013
Unsupported API method call.

Category:
Security

Cause:
Unsupported API method call.

Action:
Check the policy provider.

JPS-03014
Failed to distribute policy by timer.

Category:
Configuration

Cause:
Failed to distribute policy by timer.

Action:
Check the log for more details or contact the administator.

JPS-03015
Resource-Actions "{0}" will be skipped in bulk authorization evaluation for Application: "{1}".

Category:
Configuration

Cause:
Application name not set in the resource-actions.

Action:
Set the Application name in the resource-actions

JPS-03016
Resource-Actions "{0}" will be skipped in bulk authorization. Reason: "{1}"

Category:
Configuration

Cause:
Failed to convert the Resource-Actions into a Permission instance.

Action:
Check the logs for more information to resolve the error.

JPS-03017
Failed to compute Application roles for Subject "{0}". Reason "{1}"

Category:
Configuration

Cause:
Unable to get the ApplicationRoles granted to a principal.

Action:
Check the logs for more information to resolve the error.

JPS-03018
The authorization result is ignoring policies from application {0} as the application is not available

Category:
Configuration

Cause:
The application is not available at runtime, or the application is not defined in the policystore.

Action:
Check if the application is provisioned in the policystore.

JPS-03019
Policy evaluation in the application {0} failed. Reason: {1}

Category:
Configuration

Cause:
Error occurred while evaluating policies.

Action:
Refer to the logs to rectify the problem.

JPS-03020
Policy evaluation in the system policy failed. Reason: {0}

Category:
Configuration

Cause:
Error occurred while evaluating system policies.

Action:
Refer to the logs to rectify the problem.

JPS-03021
Admin Policy evaluation in the application {0} failed. Reason: {1}

Category:
Configuration

Cause:
Error occurred while evaluating administrative policies.

Action:
Refer to the logs to rectify the problem.

JPS-03022
Failed to initialize PolicyStore for Discovery mode. Reason: {0}

Category:
Configuration

Cause:
Failed to initialize PolicyStore for Discovery mode. Reason: {0}

Action:
Refer to the logs to rectify the problem.

JPS-03023
Discovered policy directory either not exist or can not write, isExist={0},isDirectory={1},canWrite={2}

Category:
Configuration

Cause:
Discovered policy directory either not exist or can not write, isExist={0},isDirectory={1},canWrite={2}

Action:
Make sure directory for writing discovered policy exist, is directory and can write.

JPS-03024
Failed to write policy information during discovery. Reason: {0}

Category:
Configuration

Cause:
Failed to dump policy objects in discovery mode. Reason: {0}

Action:
Refer to the logs to rectify the problem.

JPS-03025
Input permission is null when getPermissions is called for application name= {0}

Category:
Configuration

Cause:
Input permission is null when getPermissions is called. application name= {0}

Action:
Refer to the logs to rectify the problem.

JPS-03026
PDPService and PolicyStore Service instance not found in default context. Reason: {0}

Category:
Configuration

Cause:
PolicyStore service instance and PDPService service instance not found in the default JpsContext in an uncontrolled mode.

Action:
Configure a PDPService service instance in the default JpsContext, or if running in an uncontroled mode, a PolicyStore Service.

JPS-03027
PDPService service instance failed during initialization due to lack of grant. If you are seeing this error after a new installation, make sure you have updated weblogic.policy as installation step suggested

Category:
Configuration

Cause:
PDPService service instance failed during initialization because of lack of grant.

Action:
check codebase grant like weblogic.policy to see if proper grant set for all codebase of PDP service.

JPS-03028
Unable to convert to a permission entry to resource-actions entry. Reason: {0}

Category:
Configuration

Cause:
Unable to convert to a permission entry to resource-actions entry.

Action:
Check the logs for more information to resolve the error.

JPS-03029
Unable to Notify to external Application:{0} Refresh Event. Reason {1}

Category:
Configuration

Cause:
Unable to Notify to external Appliacation Refresh Event.

Action:
Check the logs for more information to resolve the error.

JPS-03030
Catch exception in PDP registration, will retry later.

Category:
Configuration

Cause:
Catch exception in PDP registration, retry later.

Action:
check the exception details and retry

JPS-03031
Catch InterruptedException in PDP registration. Registration failed.

Category:
Configuration

Cause:
Catch InterruptedException in PDP registration. Registration failed

Action:
check the exception details and retry

JPS-03032
Can not access PD server web service during PDP registration, will retry later.

Category:
Configuration

Cause:
PD Server web service not available, retry later.

Action:
wait retry to access to PD Server web service

JPS-03033
Can not access PD client web service during PDP registration, will retry later.

Category:
Configuration

Cause:
PD client web service not available, retry later.

Action:
wait retry to access to PD client web service

JPS-03034
Policystore is not ready on admin server during PDP registration, will retry later.

Category:
Configuration

Cause:
Policystore isn't available from admin server, retry later.

Action:
wait retry accessing policystore

JPS-03035
PDP registration succeeded.

Category:
Configuration

Cause:

Action:

JPS-03036
No PDP Service is found in JPS Context {1}

Category:
Configuration

Cause:
PDPService service instance is not found in JPS Context.

Action:
Configure a PDPService service instance in JPS Context

JPS-03037
Exception happened during PDP initialization.

Category:
Configuration

Cause:
Exception happened during PDP Initialization

Action:
check the exception details and retry

JPS-03038
Unable to find PolicyStore or Schema Version. Check farm name and root name of policystore service instance in OPSS configuration file.

Category:
Configuration

Cause:
Unable to find PolicyStore or Schema Version.

Action:
Check farm name and root name of policystore service instance in OPSS configuration file

JPS-03039
Exception {0} happened during Policystore agent processing message {1}, the message will be ignored.

Category:
Configuration

Cause:
Exception happened during PolicyStore agent processing

Action:
check the exception details and retry

JPS-03040
Subject resolver cache initiation failed.

Category:
Security

Cause:
Subject resolver cache initiation failed.

Action:
Make sure all jars are included in the classpath.

JPS-03041
Subject resolver cache property, key: {0}, value: {1} is not valid.

Category:
Security

Cause:
Subject resolver cache property, key: {0}, value: {1} is not valid.

Action:
Check pdp service configuration.

JPS-03042
PDP Service property, key: {0}, value: {1} is not valid, use default value: {2}.

Category:
Security

Cause:
PDP Service property, key: {0}, value: {1} is not valid, use default value: {2}.

Action:
Check pdp service configuration.

JPS-03043
Configuration property, key: {0}, value: {1} is not valid, use default value: {2}.

Category:
Security

Cause:
Configuration property, key: {0}, value: {1} is not valid, use default value: {2}.

Action:
Check pdp service configuration.

JPS-03044
Mandatory property {0} of PDP service is missing.

Category:
Configuration

Cause:
Mandatory property of PDP service is missing.

Action:
provide the required property

JPS-03045
Can not clean application : {0} from runtime cache. Reason:mode : {1} it is not non-controlled mode or not non-bound application in mixed mode.

Category:
Security

Cause:
Can not clean application : {0} from runtime cache. Reason: mode : {1} it is not non-controlled mode or not non-bound application in mixed mode.

Action:
Check pdp service configuration.

JPS-03046
Application {0} is not found when being preloaded.

Category:
Programmatic

Cause:
Application {0} is not found when being preloaded.

Action:
Please check policy store, application might have been deleted.

JPS-03047
Upsupported preload key type {0} with condition oracle.security.jps.policystore.policy.lazy.load.enable being {1} .

Category:
Programmatic

Cause:
Upsupported preload key type {0} with condition 'oracle.security.jps.policystore.policy.lazy.load.enable' being {1}

Action:
Please check the preload key and the configuration parameters for PDP service.

JPS-03048
Unable to remove application {0} from runtime cache, due to {1}

Category:
Security

Cause:
Unable to remove application {0} from runtime cache, due to {1}

Action:
Check full stacktrace

JPS-03049
Cannot {0} {1} {2} {3} because the policy lockdown has been enabled.

Category:
Security

Cause:
Cannot {0} {1} {2} {3} because the policy lockdown has been enabled

Action:
The exception is because of violation of policy customization rule. Seeded policy definition can not be modified.

JPS-03150
Error during setting the field of a provider MBean. {0}

Category:
Security

Cause:
Error during setting the field of a provider MBean. {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03151
getSecurityService returning null for requested service type of {0} for realm {1}

Category:
Security

Cause:
getSecurityService returning null for requested service type of {0} for realm {1}.

Action:
Refer to the log files for details and correct the error.

JPS-03152
Query Atz Cache specified but no response collector supplied

Category:
Security

Cause:
Query Atz Cache specified but no response collector supplied.

Action:
Supply the response collector in the request.

JPS-03153
Error parsing atz. cache flush time.

Category:
Security

Cause:
Error parsing atz. cache flush time.

Action:
Verify that the value is an integer.

JPS-03154
Authorization cache has been flushed. Time={0}

Category:
Security

Cause:
Authorization cache has been flushed. Time={0}.

Action:
No actions are required.

JPS-03155
Cannot locate class: {0}

Category:
Security

Cause:
Cannot locate class: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03156
The exception has been thrown by ARME. The authorization result is set to deny.

Category:
Security

Cause:
The exception has been thrown by ARME. The authorization result is set to deny.

Action:
Refer to the log files for details and correct the error.

JPS-03157
Error during initialization of the security framework.

Category:
Security

Cause:
Error during initialization of the security framework.

Action:
Refer to the log files for details and correct the error.

JPS-03158
Failed to parse resource cache size: {0}

Category:
Security

Cause:
Failed to parse resource cache size: {0}

Action:
Refer to the log files for details and correct the error.

JPS-03159
Invalid built in type in Value object: {0}

Category:
Security

Cause:
Invalid built in type in Value object: {0}

Action:
Refer to the log files for details and correct the error.

JPS-03160
Attempt to {0} a {1} value for type: {2}

Category:
Security

Cause:
Attempt to {0} a {1} value for type: {2}

Action:
Refer to the log files for details and correct the error.

JPS-03161
identifier not found in symbol table: {0}

Category:
Security

Cause:
Identifier not found in symbol table: {0}

Action:
Refer to the log files for details and correct the error.

JPS-03162
ERROR: PARSE: reason:==> {0}

Category:
Security

Cause:
ERROR: PARSE: reason:==>

Action:
Refer to the log files for details and correct the error.

JPS-03163
Invalid Declaration type received by setDeclType

Category:
Security

Cause:
Invalid Declaration type received by setDeclType.

Action:
Refer to the log files for details and correct the error.

JPS-03164
Got exception

Category:
Security

Cause:
Got exception.

Action:
Refer to the log files for details and correct the error.

JPS-03165
Invalid declaration type found: {0}

Category:
Security

Cause:
Invalid declaration type found: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03166
Unexpected PolicyParserTokenType: {0}

Category:
Security

Cause:
Unexpected PolicyParserTokenType: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03167
Invalid attribute type: {0}

Category:
Security

Cause:
Invalid attribute type: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03168
Invalid attribute value type: {0}

Category:
Security

Cause:
Invalid attribute value type: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03169
Invalid configuration

Category:
Security

Cause:
Invalid configuration.

Action:
Refer to the log files for details and correct the error.

JPS-03170
Try to get {0}, but JPS Policy tree is not available.

Category:
Security

Cause:
Try to get {0}, but JPS Policy tree is not available.

Action:
Refer to the log files for details and correct the error.

JPS-03171
Unable to update policy: unable to get {0} instance

Category:
Security

Cause:
Unable to update policy: unable to get {0} instance.

Action:
Refer to the log files for details and correct the error.

JPS-03172
Unspecified error in {0}

Category:
Security

Cause:
Unspecified error in {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03173
Commit error: {0}

Category:
Security

Cause:
Commit error: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03174
ARME can not find state.chk file.

Category:
Security

Cause:
ARME can not find state.chk file.

Action:
Refer to the log files for details and correct the error.

JPS-03175
Invalid mac found in write check, rewrite policies and mac

Category:
Security

Cause:
!!!>>>Invalid mac found in write check, rewrite policies and mac

Action:
Refer to the log files for details and correct the error.

JPS-03176
Failed to write check file.

Category:
Security

Cause:
Failed to write check file.

Action:
Refer to the log files for details and correct the error.

JPS-03177
Failed to close check file writer

Category:
Security

Cause:
Failed to close check file writer.

Action:
Refer to the log files for details and correct the error.

JPS-03178
Failed to write mac, which will cause Mac verification error in the future.

Category:
Security

Cause:
Failed to write mac, which will cause Mac verification error in the future.

Action:
Refer to the log files for details and correct the error.

JPS-03179
Prepare request in invalid state for update

Category:
Security

Cause:
Prepare request in invalid state for update.

Action:
Refer to the log files for details and correct the error.

JPS-03180
Error happens: {0}

Category:
Security

Cause:
Error happened: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03181
ArmeRuntimeException happens

Category:
Security

Cause:
ArmeRuntimeException happened.

Action:
Refer to the log files for details and correct the error.

JPS-03182
Cannot get AppGuardInstance, so cannot get information to request policy update from PD.

Category:
Security

Cause:
Cannot get AppGuardInstanceii, so cannot get information to request policy update from PD.

Action:
Refer to the log files for details and correct the error.

JPS-03183
Internal error. The local PD registration is required but LocalPdPort object has not been set. The registration process cannot be completed.

Category:
Security

Cause:
Internal error. The local PD registration is required but LocalPdPort object has not been set. The registration process cannot be completed.

Action:
Refer to the log files for details and correct the error.

JPS-03184
No host specified in the ARME configuration, attempting to determine host address...

Category:
Security

Cause:
No host specified in the ARME configuration, attempting to determine host address...

Action:
No actions are required.

JPS-03185
No {0} found in the ARME configuration. Cannot contact PD

Category:
Security

Cause:
No {0} found in the ARME configuration. Cannot contact PD.

Action:
Verify configuration.

JPS-03186
InstanceName not found in ARME configuration, using LocalName and host

Category:
Security

Cause:
InstanceName not found in arme configuration, using LocalName and host.

Action:
Refer to the log files for details and correct the error.

JPS-03187
No {0} from ARME, unable to contact PD

Category:
Security

Cause:
No {0} from ARME, unable to contact PD.

Action:
Refer to the log files for details and correct the error.

JPS-03188
Exception initializing SSL. Unable to contact PD

Category:
Security

Cause:
Exception initializing SSL. Unable to contact PD.

Action:
Refer to the log files for details and correct the error.

JPS-03189
Error getting attribute: {0}

Category:
Security

Cause:
Error getting attribute: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03190
Failed to close File reader while reading salt.

Category:
Security

Cause:
Failed to close File reader while reading salt.

Action:
Refer to the log files for details and correct the error.

JPS-03191
Could not obtain digest algorithm {0}

Category:
Security

Cause:
Could not obtain digest algorithm '{0}'.

Action:
Refer to the log files for details and correct the error.

JPS-03192
Index of ListValue is wrong

Category:
Security

Cause:
Index of ListValue is wrong.

Action:
Refer to the log files for details and correct the error.

JPS-03193
PBEService is not initialized

Category:
Security

Cause:
PBEService is not initialized.

Action:
Refer to the log files for details and correct the error.

JPS-03194
Port is not number type

Category:
Security

Cause:
Port is not number type.

Action:
Verify that the port value is an integer.

JPS-03195
Can not get host IP information, using default IP address: {0}

Category:
Security

Cause:
Cannot get host IP information, use default IP address: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03196
Can not get host IP information.

Category:
Security

Cause:
Cannot get host IP information.

Action:
Refer to the log files for details and correct the error.

JPS-03197
ARME shutdown failed: {0}

Category:
Security

Cause:
ARME shutdown failed: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03198
Can not get enablePerfStats from ARME config file

Category:
Security

Cause:
Cannot get enablePerfStats from arme config file.

Action:
Refer to the log files for details and correct the error.

JPS-03199
Configuration file is [{0}]

Category:
Security

Cause:
Configuration file is [{0}].

Action:
No actions are required.

JPS-03200
getDebugStore: IOException caught.

Category:
Security

Cause:
getDebugStore: IOException happens.

Action:
Refer to the log files for details and correct the error.

JPS-03201
Privilege name error: {0}

Category:
Security

Cause:
privilege name error: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03202
Resource name or application name invalid.

Category:
Security

Cause:
Resource name or application name invalid.

Action:
Refer to the log files for details and correct the error.

JPS-03203
Resource name is wrong according to ALES naming logic

Category:
Security

Cause:
Pesource name is wrong according to ALES naming logic.

Action:
Refer to the log files for details and correct the error.

JPS-03204
Invalid object name

Category:
Security

Cause:
Invalid object name.

Action:
Refer to the log files for details and correct the error.

JPS-03205
Logical name {0} is invalid

Category:
Security

Cause:
Logical name {0} is invalid.

Action:
Refer to the log files for details and correct the error.

JPS-03206
Logical name {0} is undefined

Category:
Security

Cause:
Logical name {0} is undefined.

Action:
Refer to the log files for details and correct the error.

JPS-03207
IOException occurred when storing logical names {0}

Category:
Security

Cause:
ioexception occured when storing logical names {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03208
Logical names record is not correct

Category:
Security

Cause:
Logical names record is not correct.

Action:
Refer to the log files for details and correct the error.

JPS-03209
objectTree is initialized properly

Category:
Security

Cause:
ObjectTree is initialized properly.

Action:
No actions are required.

JPS-03210
Can not close data files: {0}

Category:
Security

Cause:
Cannot close data files: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03211
Blocking queue is broken

Category:
Security

Cause:
Blocking queue is broken.

Action:
Refer to the log files for details and correct the error.

JPS-03212
Session data could not be loaded. Session abandoned

Category:
Security

Cause:
Session data could not be loaded. Session abandoned.

Action:
Refer to the log files for details and correct the error.

JPS-03213
args value is null or wrong type

Category:
Security

Cause:
Args value is null or wrong type.

Action:
Refer to the log files for details and correct the error.

JPS-03214
Could not add attribute(s) to cache

Category:
Security

Cause:
Could not add attribute(s) to cache.

Action:
Refer to the log files for details and correct the error.

JPS-03215
Caught BadParameterException during get attribute: {0}

Category:
Security

Cause:
Caught BadParameterException while getting attribute: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03216
Installing custom retriever: {0}

Category:
Security

Cause:
Installing custom retriever: {0}.

Action:
No actions are required.

JPS-03217
Caught exception while retrieving attribute from context: {0} Continue retrieving static attribute value.

Category:
Security

Cause:
Caught exception while retrieving attribute from context: {0} Continue retrieving static attribute value.

Action:
Refer to the log files for details and correct the error.

JPS-03218
Failed to transport AttributeValue to AttributeElement, caught {0}: {1}

Category:
Security

Cause:
Failed to transport AttributeValue to AttributeElement, caught {0}: {1}.

Action:
Refer to the log files for details and correct the error.

JPS-03219
AttributeValue type error, not single and list, return null

Category:
Security

Cause:
AttributeValue type error, not single and list, return null.

Action:
Refer to the log files for details and correct the error.

JPS-03220
Exception from the LDAP/DB server, code: {0}, trying alternate connection

Category:
Security

Cause:
Exception from the LDAP/DB server, code: {0}, trying alternate connection.

Action:
Refer to the log files for details and correct the error.

JPS-03221
Alternate LDAP/DB connection failed, code: {0}

Category:
Security

Cause:
Alternate LDAP/DB connection failed, code: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03222
Null extendedContext is passed to attribute retriever, cannot look for value.

Category:
Security

Cause:
Null extendedContext is passed to attribute retriever, cannot look for value.

Action:
Refer to the log files for details and correct the error.

JPS-03223
Caught exception while retrieving attribute: {0}

Category:
Security

Cause:
Caught exception while retrieving attribute: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03224
Parameter value is null or wrong type.

Category:
Security

Cause:
Parameter value is null or wrong type.

Action:
Refer to the log files for details and correct the error.

JPS-03225
Calling RBACEvals:{0}

Category:
Security

Cause:
Calling RBACEvals:{0}.

Action:
No actions are required.

JPS-03226
Empty Application name or Obligation name is passed to report_obligation function.

Category:
Security

Cause:
Empty Application name or Obligation name is passed to report_obligation function.

Action:
Refer to the log files for details and correct the error.

JPS-03227
Unexpected error: invalid parameter instances.

Category:
Security

Cause:
Unexpected error: invalid parameter instances.

Action:
Refer to the log files for details and correct the error.

JPS-03228
The value of args is null

Category:
Security

Cause:
args is null.

Action:
Refer to the log files for details and correct the error.

JPS-03229
Error during initialization of RetrieverConfiguration.

Category:
Security

Cause:
Error during initialization of RetrieverConfiguration.

Action:
Refer to the log files for details and correct the error.

JPS-03230
args value type is null or wrong type value

Category:
Security

Cause:
args value type is null or wrong type value.

Action:
Refer to the log files for details and correct the error.

JPS-03231
{0} supplied to subject_in_group is not a qualified group, will qualify

Category:
Security

Cause:
{0} supplied to subject_in_group is not a qualified group, will qualify.

Action:
Refer to the log files for details and correct the error.

JPS-03232
Qualified group is {0}

Category:
Security

Cause:
qualified group is {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03233
Type of args should be String[]

Category:
Security

Cause:
args should be String[].

Action:
Refer to the log files for details and correct the error.

JPS-03234
No value is passed to {0}

Category:
Security

Cause:
No value is passed to {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03235
No attribute name is passed to sys_obj_exists

Category:
Security

Cause:
No attribute name is passed to sys_obj_exists.

Action:
Refer to the log files for details and correct the error.

JPS-03236
Failed to get attribute {0} for eval function {0}

Category:
Security

Cause:
Failed to get attribute {0} for eval function {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03237
Value passed to {0} is not valid, {1}

Category:
Security

Cause:
Value passed to {0} is not valid, {1}.

Action:
Refer to the log files for details and correct the error.

JPS-03238
{0} is not a valid value for {1}

Category:
Security

Cause:
{0} is not a valid value for {1}.

Action:
Refer to the log files for details and correct the error.

JPS-03239
valid_timeval called for unexpected eval function {0}

Category:
Security

Cause:
valid_timeval called for unexpected eval function {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03240
Unknown eval function {0} used in valid_until_timeofday

Category:
Security

Cause:
Unknown eval function {0} used in valid_until_timeofday.

Action:
Refer to the log files for details and correct the error.

JPS-03241
Disabling extended performance data...

Category:
Security

Cause:
Disabling extended performance data...

Action:
No actions are required.

JPS-03242
The extended performance data have been retrieved. The total number of attributes is {0}, the total number of functions is {1}.

Category:
Security

Cause:
The extended performance data have been retrieved. The total number of attributes is {0}, the total number of functions is {1}.

Action:
No actions are required.

JPS-03243
Unexpected MBean attribute get method: {0}

Category:
Security

Cause:
Unexpected mbean attribute get method: {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03244
{0} specified but no response collector supplied

Category:
Security

Cause:
{0} specified but no response collector supplied.

Action:
Refer to the log files for details and correct the error.

JPS-03245
Received {0} in isProtectedResource

Category:
Security

Cause:
Received {0} in isProtectedResource.

Action:
Refer to the log files for details and correct the error.

JPS-03246
Role object passed into wles atz provider is null, ignoring

Category:
Security

Cause:
Null role object passed into wles atz provider, ignoring.

Action:
Refer to the log files for details and correct the error.

JPS-03247
A SecurityRole object passed to the authorization engine has role name equal to null. The object will be ignored. The string representation of the object is {0}.

Category:
Security

Cause:
A SecurityRole object passed to the authorization engine has role name equal to null. The object will be ignored. The string representation of the object is {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03248
Error {0}

Category:
Security

Cause:
Error {0}.

Action:
Refer to the log files for details and correct the error.

JPS-03249
ASI shutdown failed

Category:
Security

Cause:
ASI shutdown failed.

Action:
Refer to the log files for details and correct the error.

JPS-03250
getInstance: Warning: The parent classloaders are different.

Category:
Security

Cause:
getInstance: Warning: The parent classloaders are different.

Action:
Refer to the log files for details and correct the error.

JPS-03251
addClassJars: {0}

Category:
Security

Cause:
addClassJars: {0}.

Action:
Refer to the log files for details.

JPS-03252
Missing JAR file: {0}

Category:
Security

Cause:
Missing JAR file: {0}.

Action:
Refer to the log files for details.

JPS-03253
Error initializing URLs in classloader. Vector: {0}

Category:
Security

Cause:
Error initializing URLs in classloader. Vector: {0}.

Action:
Refer to the log files for details.

JPS-03254
lazy getRoles failed with error {0}

Category:
Security

Cause:
lazy getRoles failed with error {0}.

Action:
Refer to the log files for details.

JPS-03255
null value returned in roles list, ignoring

Category:
Security

Cause:
null value returned in roles list, ignoring.

Action:
Refer to the log files for details.

JPS-03256
Internal error. Method queryRoles has returned role {0} that starts with an incorrect prefix for a role. The role will be ignored.

Category:
Security

Cause:
Internal error. Method queryRoles has returned role {0} that starts with an incorrect prefix for a role. The role will be ignored.

Action:
Refer to the log files for details.

JPS-03257
Passed an non URLResource, in getAttributeValue

Category:
Security

Cause:
Passed a non URLResource, in getAttributeValue.

Action:
Refer to the log files for details.

JPS-03258
Initializing UserUtils; {0}

Category:
Security

Cause:
Initializing UserUtils; {0}.

Action:
No actions are required.

JPS-03259
Invalid built in type received

Category:
Security

Cause:
Invalid built in type received.

Action:
Refer to the log files for details.

JPS-03260
Attempt to {0} when CRED is wrong type

Category:
Security

Cause:
Attempt to {0} when CRED is wrong type.

Action:
Refer to the log files for details.

JPS-03261
No locally defined evaluator found for function {0}.

Category:
Security

Cause:
No locally defined evaluator found for function {0}.

Action:
Refer to the log files for details.

JPS-03262
DiscoveryModeRoleMap does not support this operation

Category:
Configuration

Cause:
DiscoveryModeRoleMap does not support this operation

Action:
Do not call method not supported

JPS-03263
DiscoveryModeRoleMap never contains data

Category:
Configuration

Cause:
DiscoveryModeRoleMap never contains data

Action:
Do not try to get data from DiscoveryModeRoleMap.

JPS-03264
The attribute dependency leads to a dead loop, {1} depends on {0} already.

Category:
Security

Cause:
The attribute dependency leads to a dead loop, {1} depends on {0} already.

Action:
Please check the configuration.

JPS-03265
Data source based DB query failed, try again.

Category:
Security

Cause:
Data source based DB query failed, try again.

Action:
Refer to the log files for details.

JPS-03266
Failed to retrieve connection for url {0} due to following exception {1}.

Category:
Security

Cause:
Failed to retrieve connection for {0}.

Action:
Refer to the log files for details.

JPS-03267
Ignoring credential variable exception in computeObligation for {0}.

Category:
Security

Cause:

Action:

JPS-03268
In Policy {0}, an invalid Resource Name Expression {1} was encountered. The Policy will not participate in the runtime authorization evaluation. Reason: {2}

Category:
Security

Cause:
Resource name expression in policy is invalid

Action:
Correct the reource name expression.

JPS-03269
Size of bag provided for type-one-and-only function is not one.

Category:
Programmatic

Cause:
Size of bag provided to type one and only function is not one.

Action:
Provide correct function.

JPS-03270
Invalid value of year {0} or month {1} in yearMonthDuration .Must be between max and min values for integer.

Category:
Programmatic

Cause:
Value provided for year or month is outside the supported integer range on this JVM.

Action:
Provide a valid integer value.

JPS-03271
Function name passed to evaluator is null.

Category:
Programmatic

Cause:
Function name is null.

Action:
Provide a valid function name.

JPS-03272
No arguments passed to function {0}.

Category:
Programmatic

Cause:
No arguments passed to function.

Action:
Provide a valid function arguments.

JPS-03273
Application {0} attribute {1} is not available.

Category:
Programmatic

Cause:
Application {0} attribute {1} is not available.

Action:
None.

JPS-04000
Cannot get the default policy store.

Category:
Security

Cause:
Could not find to the default policy store.

Action:
Refer to the log files for details and correct the error.

JPS-04001
Cannot read the default policy store.

Category:
Security

Cause:
Could not read the default policy store.

Action:
Refer to the log files for details and correct the error.

JPS-04002
Cannot get application policy for application "{0}".

Category:
Security

Cause:
Encountered a policy store internal error.

Action:
Refer to the log files for details and correct the error.

JPS-04003
Duplicate principal present "{0}"in a grant request.

Category:
Security

Cause:
Found that list of principals in the grantee for the grant contains duplicate

Action:
Correct the list of principals in the grantee.

JPS-04004
Duplicate permission present "{0}" in a grant request.

Category:
Security

Cause:
Found that list of permissions in the grant contains duplicate.

Action:
Correct the list of permissions in the grant.

JPS-04005
More than one result found for given Application Name:{0}, Query:{1}, Actual results:{2}.

Category:
Security

Cause:
More than one results found for application name.

Action:
Refer to the log files for details and correct the error.

JPS-04006
No results found for given Application Name:{0}, DN: {1}, Query: {2}.

Category:
Security

Cause:
No results found for application name.

Action:
Refer to the log files for details and correct the error.

JPS-04021
Application Policy "{0}" already exists.

Category:
Security

Cause:
Encountered two application policy contexts with identical names.

Action:
Modify an application policy context to have a distinct name.

JPS-04022
Cannot create application policy context "{0}".

Category:
Security

Cause:
Failed to complete persist operation while creating an application policy.

Action:
Refer to the base exception in log files and correct the error.

JPS-04026
Application policy "{0}" does not exist.

Category:
Security

Cause:
Could not find a policy context with the provided name.

Action:
Verify that a context with the provided name exists.

JPS-04027
Role with name "{0}" does not exist.

Category:
Configuration

Cause:
Could not find a role with name {0}.

Action:
Verify that a role with the provided name exists.

JPS-04028
Application with name "{0}" does not exist.

Category:
Configuration

Cause:
Could not find application with name {0}.

Action:
Verify that an application with the provided name exists.

JPS-04029
Cannot create principal with class name "{0}".

Category:
Configuration

Cause:
Could not create principal with class name {0}.

Action:
Verify that the provided class name is valid.

JPS-04030
Cannot delete application policy context "{0}".

Category:
Security

Cause:
Failed to complete persist operation while deleting an application policy.

Action:
Refer to the base exception in log files and correct the error.

JPS-04031
Parameter "{0}" is null or empty.

Category:
Security

Cause:
Supplied parameter {0} was null or empty.

Action:
Verify that the supplied parameter is non-null. If it is of type String, ensure that its length is positive.

JPS-04032
Parameter "{0}" supplied is not the instance of "{1}".

Category:
Security

Cause:
Parameter {0} supplied is not the instance of {1}.

Action:
Ensure parameter is of correct datatype.

JPS-04033
Parameter "{0}" supplied is not of the type "{1}" (as expected).

Category:
Security

Cause:
Parameter {0} supplied is not of the type {1} (as expected).

Action:
Ensure parameter is of correct datatype.

JPS-04034
Failed to modify properties for Application "{0}".

Category:
Security

Cause:
Cannot modify application policy.

Action:
Check the logs for errors.

JPS-04035
AttributeName {0} supplied should start with alphabet or an underscore. Name cannot contain characters other than alphanumeric and/or underscores.

Category:
Security

Cause:
AttributeName {0} supplied should start with alphabet or an underscore. Name cannot contain characters contain other than alphanumeric and/or underscores.

Action:
Ensure attribute name is of correct datatype.

JPS-04036
Function Name {0} supplied should start with alphabet or an underscore. Name cannot contain characters other than alphanumeric and/or underscores.

Category:
Security

Cause:
Function Name {0} supplied should start with alphabet or an underscore. Name cannot contain characters contain other than alphanumeric and/or underscores.

Action:
Ensure function name is of correct datatype.

JPS-04037
Name "{0}" starts or ends with whitespace.

Category:
Security

Cause:
Object name should not start with or end with whitespace.

Action:
Ensure object name has no whitespace in the beginning and end.

JPS-04038
Object name only contains whitespace.

Category:
Security

Cause:
Object name should not only contain whitespace.

Action:
Ensure object name doesn't only contain whitespace.

JPS-04039
Application "{0}", Deleting {1} entries under "{2}", Maximum remaining re-tries {3}.

Category:
Security

Cause:

Action:

JPS-04080
Scanning of system policy failed. Reason {0}

Category:
Security

Cause:
Scan of system policy failed.

Action:
Check the system policy setup and the provider setup.

JPS-04081
Policy store purge thread interrupted. Reason {0}.

Category:
Security

Cause:
Purge thread interrupted in policy caching.

Action:
Check the policy setup and the provider setup

JPS-04082
Deletion of system policy failed. Reason {0}

Category:
Security

Cause:
Deletion of system policy failed.

Action:
Provide legal non empty values for policy name

JPS-04083
Creation of system policy failed. Reason {0}

Category:
Security

Cause:
Creation of system policy failed.

Action:
Provide legal non empty values for policy name

JPS-04084
Migration of application policy failed. Further migration of application policies halted. Reason: {0}.

Category:
Security

Cause:
Exception in migration of application policy

Action:
Check application policy setup or contact system administrator

JPS-04085
Migration of codebase policy failed. Reason: {0}.

Category:
Security

Cause:
Exception in migration of codebase policy

Action:
Check codebase policy setup or contact system administrator

JPS-04086
Could not perform isPolicyModified. Reason {0}

Category:
Security

Cause:
Is policy modification check failed.

Action:
Contact system administrator

JPS-04089
Could not get policy cache count. Reason {0}

Category:
Security

Cause:
Could not retrieve policy cache count.

Action:
Contact system administrator

JPS-04090
The policy store property {0} is invalid or not defined.

Category:
Requests/Responses

Cause:
The policy store property {0} was invalid or not defined.

Action:
Check the configuration of this property.

JPS-04091
Application {0} is being deployed with policy migration option set to {1}, start policy migration.

Category:
Security

Cause:
Start application policy migration

Action:
No action required

JPS-04092
Application {0} is being deployed with policy migration option set to neither OVERWRITE nor MERGE, skip policy migration.

Category:
Security

Cause:
Skip application policy migration

Action:
No action required

JPS-04093
Application policy migration for application {0} is completed successfully.

Category:
Security

Cause:
Complete application policy migration

Action:
No action required

JPS-04094
Start removing application policies for Application {0}.

Category:
Security

Cause:
Start application policy removal

Action:
No action required

JPS-04095
Application policy removal for application {0} is completed successfully.

Category:
Security

Cause:
Complete application policy removal

Action:
No action required

JPS-04096
Application policies for application {0} was NOT removed in application undeployment with jps.policystore.removal set to OFF.

Category:
Security

Cause:
Skip application policy removal

Action:
No action required

JPS-04097
Application {0} is being deployed without existing application policies found in static deployment, start policy migration.

Category:
Security

Cause:
Start application policy migration in static deployment

Action:
No action required

JPS-04098
Start codebase policy migration for application {0}.

Category:
Security

Cause:
Start codebase policy migration

Action:
No action required

JPS-04099
Codebase policy migration for {0} is completed successfully.

Category:
Security

Cause:
Complete codebase policy migration

Action:
No action required

JPS-04100
Application Role "{0}" already exists.

Category:
Security

Cause:
Encountered two roles with identical names.

Action:
Modify a role to have a distinct name.

JPS-04101
Cannot create application role "{0}".

Category:
Security

Cause:
Failed to complete persist operation while creating an application role.

Action:
Refer to the base exception in logs to resolve the issue.

JPS-04102
Cannot create application role. Cause: Invalid Argument -- Multiple role categories supplied for single application role

Category:
Security

Cause:
Persist operation failed because more than one role category supplied for create role

Action:
Ensure supplied parameters are correct.

JPS-04110
Cannot delete application role "{0}". Cause: Application role not found.

Category:
Security

Cause:
Could not find an application role in the application policy.

Action:
Check the name of the application role.

JPS-04111
Cannot delete application role "{0}".

Category:
Security

Cause:
Could not remove application role from policy store.

Action:
Refer to the base exception in log files and correct the error.

JPS-04112
Cannot delete application role "{0}".

Category:
Security

Cause:
Could not remove application role "{0}" because it may be in use; this role is a member of one or more other application roles (nested role hierarchy).

Action:
Flatten the nested role hierarchy, and then remove the desired role. Alternatively, remove the application role using the option force set to true.

JPS-04113
Cannot delete application role "{0}".

Category:
Security

Cause:
Could not remove application role "{0}" because it may be in use, or contains enterprise groups or enterprise users.

Action:
Remove the enterprise groups and enterprise users from the application role, or remove the application role using the option force set to true.

JPS-04114
Cannot delete application role "{0}".

Category:
Security

Cause:
Could not remove application role "{0}" because it may be in use; this role has one or more permissions granted to it.

Action:
Revoke the permission(s) from the application role, and then remove the role. Alternatively, remove the application role using the option force set to true.

JPS-04120
Cannot add principal to application role.

Category:
Security

Cause:
Encountered an internal policy store error.

Action:
Refer to the base exception in log files and correct the error.

JPS-04121
Cannot add principal to application role "{0}".

Category:
Security

Cause:
Could not find application role in the application policy context.

Action:
Ensure the application role is present in the application policy.

JPS-04122
Cannot add principal to application role; principal(s) "{0}" is already a member of application role "{1}".

Category:
Security

Cause:
Found that principal {0} is already a member of the application role {1}.

Action:
Correct the principal name.

JPS-04123
Cannot add principal to the application role.

Category:
Security

Cause:
Attempted to insert an application role as a member of itself.

Action:
Correct the application role principal name. The containment in the role hierarchy must be cycle-free.

JPS-04124
The application role {0} added to {1} has no GUID defined.

Category:
Requests/Responses

Cause:
The application role {0} added to {1} has no GUID defined.

Action:
Ensure the application role has GUID before adding it as a member of an application role.

JPS-04125
Application Role {0} granted to role category {1} cannot be found in application {2}

Category:
Security

Cause:
Application Role {0} granted to role category {1} cannot be found in application {2}

Action:
Ensure application role exists before assigning it to a role category

JPS-04130
Cannot remove principal from application role.

Category:
Security

Cause:
Encountered an internal policy store error.

Action:
Refer to the base exception in log files and correct the error.

JPS-04131
Cannot remove principal from application role; cannot find application role "{0}" in application policy context.

Category:
Security

Cause:
Could not find the specified application role in the application policy context.

Action:
Correct the application role name.

JPS-04132
Cannot remove principal from application role; principal "{0}" is not member of application role "{1}".

Category:
Security

Cause:
See error message.

Action:
Correct the principal role name.

JPS-04135
Resource name not specified in application {0}.

Category:
Security

Cause:
Resource name not specified in application {0}.

Action:
Ensure the resource name is not null.

JPS-04136
Resource type name not specified in application {0}.

Category:
Security

Cause:
Resource type name not specified in application {0}.

Action:
Ensure the resource type name is not null.

JPS-04137
Permission set name not specified in application {0}.

Category:
Security

Cause:
Permission set name not specified in application {0}.

Action:
Ensure the permission set name is not null.

JPS-04138
Application role name not specified in application {0}.

Category:
Security

Cause:
Application role name not specified in application {0}.

Action:
Ensure the application role name is not null.

JPS-04140
Cannot complete application role search because search expression "{0}" is incorrect.

Category:
Security

Cause:
Found an invalid search pattern.

Action:
Refer to the base exception in log files and correct the error.

JPS-04141
Cannot complete application role search because of internal error {0}.

Category:
Security

Cause:
Encountered an internal policy store error while searching the policy store.

Action:
Refer to the base exception in log files and correct the error.

JPS-04142
Cannot complete application role search because search role attribute "{0}" is incorrect.

Category:
Security

Cause:
Could not complete the search because the application role attribute {0} was invalid.

Action:
Supply a valid role attribute name.

JPS-04143
Cannot find application role "{0}".

Category:
Security

Cause:
Could not find application role in the application policy context.

Action:
Supply the name of an existing application role name.

JPS-04144
Cannot get granted application role for principal "{0}".

Category:
Security

Cause:
Encountered an internal policy store error.

Action:
Refer to the base exception in log files and correct the error.

JPS-04145
Cannot get all application roles for application "{0}".

Category:
Security

Cause:
Encountered an internal policy store error.

Action:
Refer to the base exception in log files and correct the error.

JPS-04146
Cannot complete application role search because search role attribute name is null.

Category:
Security

Cause:
Could not complete the search because the role attribute name was NULL.

Action:
Provide a non-null role attribute name.

JPS-04147
Cannot get members of application role "{0}".

Category:
Security

Cause:
Could not find application role in the application policy context.

Action:
Supply the name of an existing application role name.

JPS-04148
Exception when converting "{0}" to number, msg is "{1}".

Category:
Security

Cause:
Exception when converting {0} to number, msg is {1}

Action:
Only number is allowed

JPS-04150
Cannot alter application role {0} since multiple entries found for the application name:{1} query: {2} and actual result is {3}.

Category:
Security

Cause:
Encountered the policy store error {0}.

Action:
Check the error details to resolve the issue.

JPS-04151
Cannot alter application role.

Category:
Security

Cause:
Could not find application role {0} in the application policy context.

Action:
Provide an existing application role name.

JPS-04153
In Domain {0}, Application {1} is not present.

Category:
Security

Cause:
Application not found in the policystore

Action:
Check the name of the application in the policystore.

JPS-04154
Refresh of application policy failed. Reason {0}

Category:
Security

Cause:
Refresh of application policy failed.

Action:
Check the application policy setup and the provider setup

JPS-04155
Scanning of application policy failed. Reason {0}

Category:
Security

Cause:
Scan of application policy failed.

Action:
Check the application policy setup and the provider setup

JPS-04156
RoleCategory modification attribute "{0}" is invalid.

Category:
Security

Cause:
Invalid RoleCategory modify attribute

Action:
Check whether the attribute you are trying to modify is valid or not.

JPS-04157
RoleCategory "{0}" already exists.

Category:
Security

Cause:
The role category already exists.

Action:
Supply a different role category name.

JPS-04158
RoleCategory {0} does not exist

Category:
Security

Cause:
The role category does not exist.

Action:
Supply a different role category name.

JPS-04159
Role category search value: {0}, is invalid for matcher type: {1}

Category:
Security

Cause:
The role category search query has invalid parameter value

Action:
Modify the search query and supply correct parameter value.

JPS-04160
Cannot find PermissionSet {0} in policy store.

Category:
Security

Cause:
Could not find PermissionSet in policy store.

Action:
Provide the name of a valid PermissionSet.

JPS-04161
Search for PermissionSet {0} by name yielded more than one result.

Category:
Security

Cause:
Found a duplicate PermissionSet name in search context.

Action:
Ensure that all PermissionSet names in the current search context are distinct.

JPS-04162
PermissionSet "{0}" already exists in policy store.

Category:
Security

Cause:
Permission Set already exists.

Action:
Create a PermissionSet with a different name.

JPS-04163
PermissionSet {0} cannot have empty ResourceActions.

Category:
Security

Cause:
PermissionSet {0} has empty ResourceActions.

Action:
Ensure PermissionSet has ResourceActions.

JPS-04164
MemberResource {0} of type {1} not found in application {1}.

Category:
Security

Cause:
MemberResource {0} of type {1} not found in application {1}.

Action:
Ensure the Resource exists in the PolicyStore.

JPS-04165
ResourceType {0} referenced by MemberResource {1} not found in application {2}.

Category:
Security

Cause:
ResourceType {0} referenced by MemberResource {1} not found in application {2}.

Action:
Ensure the ResourceType exists in the PolicyStore.

JPS-04166
MemberResource {0} of type {1} does not have actions defined.

Category:
Security

Cause:
MemberResource {0} of type {1} does not have actions defined.

Action:
Ensure the MemberResource has valid actions.

JPS-04167
MemberResource {0} of type {1} has actions defined.

Category:
Security

Cause:
MemberResource {0} of type {1} has actions defined.

Action:
Ensure the MemberResource does not have actions.

JPS-04168
PermissionSet {0} cannot be created without ResourceActions.

Category:
Security

Cause:
PermissionSet {0} cannot be created without ResourceActions.

Action:
Create a PermissionSet with ResourceActions.

JPS-04169
ResourceAction {0} used to modify PermissionSet {1} has invalid actions for ResourceType {2}.

Category:
Security

Cause:
ResourceAction {0} used to modify PermissionSet {1} has invalid actions for ResourceType {2}.

Action:
Modify PermissionSet using a ResourceAction that has valid actions.

JPS-04173
The resource type {0} is not found in store

Category:
Configuration

Cause:
Unsupported Resource Type {0}.

Action:
Check Resource Type.

JPS-04179
The resource type reference for resource {0} is not found in the application {1}. Hence using the first occurrence

Category:
Security

Cause:
The resource type reference for resource {0} is not found in the application {1}. Hence using the first occurrence.

Action:
Ensure the ResourceType reference exists for every resource.

JPS-04190
Cannot find resource.

Category:
Security

Cause:
Could not find resource in the resource store.

Action:
Modify your search query.

JPS-04191
Cannot find unregistered resource finder for resource type "{0}".

Category:
Security

Cause:
Could not find a registered resource finder for the resource type.

Action:
Provide a resource finder implementation for the resource type, and register it with JPS.

JPS-04192
Cannot load resource finder with provider name "{0}".

Category:
Security

Cause:
Found an incorrect implementation: argumentless public constructor is missing.

Action:
Revisit the implementation to provide an argumentless public constructor.

JPS-04193
Cannot load resource finder with provider name "{0}" and class "{1}".

Category:
Security

Cause:
Could not load resource finder class: error encountered while reading a registered class file for resource finder.

Action:
Check the configuration of the class property in jps-config.xml.

JPS-04194
Cannot initialize resource finder with provider name "{0}" and class name "{1}".

Category:
Security

Cause:
Found an error while initializing a registered class for resource finder.

Action:
Check the configuration of the class property in jps-config.xml.

JPS-04195
Cannot load the resource finder with provider "{0}".

Category:
Security

Cause:
Found an error in external resource finder configuration: a required property was missing.

Action:
Check the configuration of the class property in jps-config.xml.

JPS-04198
Resource {0} in application {1} has a non existent resource type {2}. Ignoring this resource.

Category:
Security

Cause:
Resource {0} in application {1} has a non existent resource type {2}. Ignoring this resource.

Action:
Ensure the ResourceType exists for every resource.

JPS-04200
Cannot grant policy due to a policy store internal error.

Category:
Security

Cause:
Encountered a policy store error.

Action:
Check the error details to resolve the issue.

JPS-04201
Cannot grant permission(s). Grant already exists for grantee {0}.

Category:
Security

Cause:
Permissions already granted to grantee.

Action:
Grant a different set of permissions.

JPS-04202
Cannot revoke policy.

Category:
Security

Cause:
Encountered an internal policy store error while revoking a policy.

Action:
Refer to the base exception in log files and correct the error.

JPS-04203
Cannot revoke permission.

Category:
Security

Cause:
Found that a permission has not been granted.

Action:
Provide the appropriate permission to the grantee.

JPS-04204
Cannot revoke permissions.

Category:
Security

Cause:
Found that permissions have not been granted.

Action:
Provide the appropriate permissions to the grantee.

JPS-04205
Cannot revoke permissions.

Category:
Security

Cause:
Found that permissions have not been granted to principals.

Action:
Provide the appropriate permissions to principals.

JPS-04206
Cannot revoke permissions.

Category:
Security

Cause:
Found that permissions have not been granted to code source.

Action:
Correct the code source grantee.

JPS-04207
Matching Grantee not found: {0}.

Category:
Security

Cause:
Found that permissions have not been granted to principals or code source.

Action:
Correct the list of principals and code source in the grantee, or revoke permissions granted to this grantee.

JPS-04208
Cannot modify policy due to a policy store internal error.

Category:
Security

Cause:
Encountered an internal policy store error while modifying the policy store.

Action:
Refer to the base exception in log files and correct the error.

JPS-04209
Cannot modify property {0}.

Category:
Security

Cause:
Could not modify a property.

Action:
Supply the name of a property that can be modified.

JPS-04210
Modification code {0} is invalid.

Category:
Security

Cause:
Found an unsupported modification code.

Action:
Ensure that the modification code is ADD, REMOVE, or REPLACE.

JPS-04211
Cannot query, update, or delete Object with type "{0}" and name "{1}".

Category:
Security

Cause:
Attempted to query, update, or delete an invalid policy store object.

Action:
Ensure that the object to be queried, updated, or deleted belongs to the appropriate policy domain

JPS-04212
PermissionSet "{0}" is in use, cannot delete.

Category:
Security

Cause:
Permission set already existed.

Action:
Permission set with the same name cannot be created. Use different name.

JPS-04213
Cannot modify a grant with an empty permission entry.

Category:
Security

Cause:
Encountered empty permission entry list while modifying a grant

Action:
Pass a non empty permission entry list while modifying a grant

JPS-04216
Cannot grant/revoke permissions because type "{0} " is not known.

Category:
Security

Cause:
Resource type validation for Permission set failed

Action:
Check whether the grant's permission's resourcetype is provisioned in the policystore.

JPS-04217
Grant/revoke failed for grantee "{0}", permission class "{1}", resource name "{2}", permission actions "{3}", resource type "{4}". Reason: permission actions is not a subset of resource type actions " {5}".

Category:
Security

Cause:
Resource type validation for Permission set failed

Action:
Check whether the actions in the Permission are valid actions for the resource type provisioned in the policy store.

JPS-04218
Grant/revoke failed for grantee "{0}", permission class "{1}", resource Name "{2}", permission actions "{3}", resource type "{4}". Reason: permission class is not equal to resource type matcher class " {5}".

Category:
Security

Cause:
Resource type validation for Permission set failed

Action:
Check whether the matcher class in the Permission is valid for the resource type provisioned in the policy store.

JPS-04219
The action {0} is invalid for resource type {1}.

Category:
Requests/Responses

Cause:
The action {0} is invalid for resource type {1}.

Action:
Check the ResourceActionsEntry parameter.

JPS-04220
Cannot search because the search query "{0}" was empty (has no child query).

Category:
Requests/Responses

Cause:
The search query {0} was empty (has no child query).

Action:
Provide a non-empty search query in.

JPS-04221
Cannot search because the grant search query "{0}" has illegal object type for search property "{1}".

Category:
Security

Cause:
The grant search query {0} has wrong object type in search value for search property {1}.

Action:
Provide an object type corresponding to the search property.

JPS-04222
Cannot search because the search query was null for "{0}" .

Category:
Requests/Responses

Cause:
The search query was null for {0} .

Action:
Provide a non-null search query .

JPS-04223
Access to tenant system policy is not allowed.

Category:
Security

Cause:
Access to tenant system policy is not allowed.

Action:
Access global system policy instead.

JPS-04227
The object name "{0}" is invalid.

Category:
Requests/Responses

Cause:
The object name {0} is invalid.

Action:
Pass a correct object name in.

JPS-04300
Cannot save policy.

Category:
Security

Cause:
Could not save policy. Cause {0}.

Action:
Check the log files and resolve the error.

JPS-04301
Cannot read from policy store. Reason is {0}, {1}

Category:
Security

Cause:
Could not read from the policy store.

Action:
Check the log files and resolve the error.

JPS-04302
Cannot read from policy store.

Category:
Configuration

Cause:
Could not find the location property {1} in instance {0}.

Action:
Ensure the location is set to a valid policy store file.

JPS-04303
Cannot read from policy store.

Category:
Configuration

Cause:
Could not find value for system property '{0}' or for location property '{2}' in instance '{1}'.

Action:
Ensure the location is set to a valid policy store file.

JPS-04304
Policy store instance descriptor {0}, location value {1} is ignored.

Category:
Configuration

Cause:
Could not find value for the system property '{0}', which overrides the descriptor property {1} in the policy store service instance.

Action:
Unset the system property so that the location is picked up from configuration in jps-config.xml.

JPS-04305
Could not determine the work folder for controlled and mixed mode PD.

Category:
Configuration

Cause:
Could not determine the work folder for controlled and mixed mode PD.

Action:
Ensure system property "oracle.security.jps.config" or "domain.home" is set and jps-config.xml is present under ${domain.home}/config/fmwconfig.

JPS-04410
Cannot create JACC module policy context "{0}" for application {1}.

Category:
Security

Cause:
Could not create application policy because found two application module contexts with identical names.

Action:
Ensure that all application module context names are distinct.

JPS-04411
Cannot create application "{0}" JACC module policy context "{1}".

Category:
Security

Cause:
Could not create application module policy; persist operation failed.

Action:
Refer to the base exception in log files and correct the error.

JPS-04412
Cannot delete JACC module "{0}".

Category:
Security

Cause:
Could not find JACC policy context to delete.

Action:
Check the JACC policy context name.

JPS-04413
Cannot delete JACC module policy context "{0}".

Category:
Security

Cause:
Could not delete JACC policy; persist operation failed.

Action:
Refer to the base exception in log files and correct the error.

JPS-04420
Application policy context name is missing from application role {0}.

Category:
Security

Cause:
Could not find application policy context in the application role principal.

Action:
Ensure that the application role principal has an application context.

JPS-04421
Administrator role name is invalid.

Category:
Security

Cause:
Found an invalid administrator role name.

Action:
Correct the name of the administrator role.

JPS-04422
Policy is malformed.

Category:
Security

Cause:
Found system policy that granted permissions to application role(s).

Action:
Grants to application roles are not allowed in a system policy. Remove such grants.

JPS-04423
Application role name "{0}" is invalid.

Category:
Security

Cause:
Found invalid application role name {0}.

Action:
Verify that the application role name conforms with the role name syntax.

JPS-04502
Java SSO Login

Category:
Requests/Responses

Cause:
This was JSSO page title.

Action:
No action needed.

JPS-04503
Enter your single sign-on username and password.

Category:
Requests/Responses

Cause:
User name and password were required for logging into JSSO.

Action:
Enter a valid user name and password.

JPS-04504
Username

Category:
Requests/Responses

Cause:
This was JSSO login user name.

Action:
No action needed.

JPS-04505
Password

Category:
Requests/Responses

Cause:
This was JSSO login user password.

Action:
No action needed.

JPS-04506
Login

Category:
Requests/Responses

Cause:
Submit button.

Action:
Press submit.

JPS-04507
Cancel

Category:
Requests/Responses

Cause:
Cancel button.

Action:
Press cancel to abort login.

JPS-04508
Failed.

Category:
Requests/Responses

Cause:
JSSO login failed.

Action:
Check user name and password used for login.

JPS-04509
The maximum number of login attempts is exceeded. Contact the application administrator, or retry after {0} minutes.

Category:
Requests/Responses

Cause:
Maximum login attempts was exceeded.

Action:
Contact the system administrator.

JPS-04510
Incorrect username or password.

Category:
Requests/Responses

Cause:
User name or password was invalid.

Action:
Check the user name and password used for login.

JPS-04511
Java SSO Application Error.

Category:
Requests/Responses

Cause:
Encountered and internal error.

Action:
Contact the system administrator.

JPS-04512
application error

Category:
Requests/Responses

Cause:
Encountered and internal error.

Action:
Contact the system administrator.

JPS-04513
The Java SSO application is not properly configured.

Category:
Configuration

Cause:
The Java SSO application was not correctly configured.

Action:
Reconfigure the application.

JPS-04514
Configuration error: {0}.

Category:
Configuration

Cause:
The Java SSO application was not correctly configured.

Action:
Reconfigure the application.

JPS-04515
Usage arguments:

Category:
Requests/Responses

Cause:
Defines the keytool usage.

Action:
See error message.

JPS-04516
No key type for algorithm.

Category:
Configuration

Cause:
The algorithm key type was not specified.

Action:
Configure the algorithm key type.

JPS-04517
Key does not match any known algorithm.

Category:
Configuration

Cause:
The given key did not match the corresponding algorithm.

Action:
Reconfigure the algorithm key type.

JPS-04518
The number of JSSO cookies is zero or invalid.

Category:
Requests/Responses

Cause:
Could not find JSSO cookie in header.

Action:
Login again or contact the system administrator.

JPS-04519
The number of Oracle Access Manager cookies is zero or invalid.

Category:
Requests/Responses

Cause:
Could not find Oracle Access Manager cookie in header.

Action:
Login again or contact the system administrator.

JPS-04520
Token type is invalid: expected type is COOKIE_TOKEN, but found {0}.

Category:
Configuration

Cause:
The token type configured was invalid: it should be COOKIE_TOKEN.

Action:
Reconfigure the token type to a valid value.

JPS-04521
The JSSO property {0} is not set.

Category:
Configuration

Cause:
JSSO property was not correctly configured.

Action:
Reconfigure the property to a correct value.

JPS-04522
The authentication type {0} is invalid.

Category:
Configuration

Cause:
JSSO did not support this authentication type.

Action:
Reconfigure the type to a supported type.

JPS-04523
Token is no longer valid.

Category:
Requests/Responses

Cause:
The incoming token was no longer valid.

Action:
Login again.

JPS-04524
Cannot create token from JSSO cookie.

Category:
Requests/Responses

Cause:
Could not create token from the JSSO cookie; cookie may have expired.

Action:
Login again.

JPS-04525
The number of cookies is zero or the invalid number {0}.

Category:
Requests/Responses

Cause:
Could not find at least one cookie in the request.

Action:
Login again.

JPS-04526
Token has invalid version number.

Category:
Requests/Responses

Cause:
Token had invalid version number.

Action:
Login again.

JPS-04527
Token has an invalid format.

Category:
Requests/Responses

Cause:
Token was corrupted or had invalid format.

Action:
Login again.

JPS-04528
An error occurred while encoding JSSO token.

Category:
Configuration

Cause:
Could not encode JSSO token.

Action:
Specify a valid, supported encoding.

JPS-04529
Cannot verify signature in the JSSO token.

Category:
Requests/Responses

Cause:
Could not verify signature: the token was tampered with, or the signature algorithm was invalid.

Action:
Specify a supported signature algorithm.

JPS-04530
Algorithm is unsupported.

Category:
Configuration

Cause:
Specified algorithm was unsupported.

Action:
Check documentation for the list of supported algorithms.

JPS-04531
Error creating cipher.

Category:
Configuration

Cause:
Could not create cipher.

Action:
Check documentation for the list of supported cipher algorithms.

JPS-04532
JSSO logout URL is not configured.

Category:
Configuration

Cause:
The logout URL was not configured or invalid.

Action:
Check the logout URL configuration properties, and reconfigure it to a valid URL.

JPS-04533
JSSO has encountered an unexpected error.

Category:
Requests/Responses

Cause:
An internal error occurred.

Action:
Contact the system administrator.

JPS-04534
JSSO symmetric key is missing.

Category:
Configuration

Cause:
The symmetric key configuration was missing.

Action:
Ensure that the properties "custom.sso.cred.key" and "custom.sso.cred.alias" are configured in the service instance, and that the symmetric key is present in the credential store.

JPS-04535
Identity name is invalid.

Category:
Configuration

Cause:
User identity was invalid or missing.

Action:
Provide a valid user identity.

JPS-04536
The token name {0} is missing in request object.

Category:
Configuration

Cause:
Token name was missing in the request object.

Action:
Ensure that the token name is present in the request object.

JPS-04537
No token name is specified for token collector {0}.

Category:
Configuration

Cause:
Token collector was invalid or missing.

Action:
Configure a valid token collector with the property "idm.token.collector.class".

JPS-04538
The request object class is invalid.

Category:
Configuration

Cause:
The request object class was invalid.

Action:
Ensure that the request object is valid.

JPS-04539
Token collector is not properly initialized.

Category:
Configuration

Cause:
Could not initialize the token collector.

Action:
Ensure that the token collector is correctly configured and initialized.

JPS-04540
The token asserter is not properly initialized.

Category:
Configuration

Cause:
Could not initialize the token asserter.

Action:
Ensure that the token asserter is correctly configured and initialized.

JPS-04541
Cannot find authenticated identity.

Category:
Configuration

Cause:
Authentication failed.

Action:
Provide a valid identity.

JPS-04542
The token collector class {0} is not properly configured in the configuration file.

Category:
Configuration

Cause:
Token collector class was missing.

Action:
Configure a valid token collector class with the property "idm.token.collector.class".

JPS-04543
No login module is configured for application.

Category:
Configuration

Cause:
Could not find configured login module.

Action:
Configure a login module in jps-config.xml.

JPS-04544
The subject of the identity is invalid.

Category:
Configuration

Cause:
Subject was missing.

Action:
Ensure that the valid Subject is present.

JPS-04545
Cannot verify the Subject {0}.

Category:
Configuration

Cause:
Could not verify Subject.

Action:
Check the user credentials.

JPS-04546
The configuration (idm.subject.loginmodule.disabled=true) specifies that the Subject is populated by the token asserter.

Category:
Configuration

Cause:
Could not find Subject asserter.

Action:
Configure an asserter to use a login module that returns a valid Subject.

JPS-04547
The token type {0} is not properly configured in the configuration file.

Category:
Configuration

Cause:
Could not find token type configuration.

Action:
Configure a token type in the service instance with the property "idm.token.type property".

JPS-04548
The token asserter class {0} is not properly configured in the configuration file.

Category:
Configuration

Cause:
Could not find token asserter class configuration.

Action:
Configure a token asseter class in the service instance with the property "idm.token.asserter.class".

JPS-04549
Token is no longer valid.

Category:
Configuration

Cause:
Found invalid or expired token.

Action:
Check that the token is valid and has not expired.

JPS-04550
Token type is invalid: expected type is HEADER_TOKEN, but found {0}.

Category:
Configuration

Cause:
Token type was invalid: it should be HEADER_TOKEN.

Action:
Reconfigure the token type to a valid type.

JPS-04551
The number of OSSO headers is zero or an invalid number.

Category:
Requests/Responses

Cause:
Could not find OSSO header in HTTP request.

Action:
Login again, or contact the system administrator.

JPS-04552
The required Oracle Access Manager property {0} is missing or invalid.

Category:
Configuration

Cause:
A required Oracle Access Manager property was missing or invalid.

Action:
Configure the property "access.sdk.install.path" in the service instance in jps-config.xml.

JPS-04553
The user identity {0} for Oracle Access Manager is invalid.

Category:
Requests/Responses

Cause:
The user identity for Oracle Access Manager was invalid.

Action:
Login again.

JPS-04554
The user password for Oracle Access Manager is invalid.

Category:
Requests/Responses

Cause:
The user password for Oracle Access Manager was invalid.

Action:
Login again.

JPS-04555
The user {0} is not logged in to Oracle Access Manager. The error is {1}.

Category:
Requests/Responses

Cause:
The user was not logged in Oracle Access Manager.

Action:
Login again.

JPS-04556
The user {0} is not authorized to access a resource type authentication in Oracle Access Manager.

Category:
Requests/Responses

Cause:
The user was not logged in Oracle Access Manager.

Action:
Login again.

JPS-04557
Invalid parameter {0} supplied. Cannot be null or empty.

Category:
Requests/Responses

Cause:
Invalid parameter {0} supplied. Cannot be null or empty.

Action:
Ensure the parameter is not null or empty.

JPS-04558
The SSO service is not properly configured: {0}.

Category:
Configuration

Cause:
The SSO service is not properly configured: {0}.

Action:
Check the SSO Service configuration.

JPS-04559
Failed to create the {0} token. Cause: {1}.

Category:
Requests/Responses

Cause:
Failed to create the {0} token. Cause: {1}.

Action:
Re-login.

JPS-04560
SSO provider cannot initiate SSO process: {0}.

Category:
Requests/Responses

Cause:
SSO provider cannot initiate SSO process: {0}.

Action:
Check the SSO Service configuration.

JPS-04561
Invalid parameter {0} supplied. Cannot be null.

Category:
Requests/Responses

Cause:
Invalid parameter {0} supplied. Cannot be null.

Action:
Ensure the parameter is not null.

JPS-04601
Cannot obtain audit service for policy store.

Category:
Security

Cause:
Could not query audit service about audit logging level for policy store messages.

Action:
Ensure that auditing is configured correctly.

JPS-04602
Cannot log policy management event to the audit service.

Category:
Security

Cause:
Could not log policy management audit messages to the audit service.

Action:
Ensure that auditing is configured correctly in your environment and application.

JPS-05500
Cannot create the user manager MBean.

Category:
Configuration

Cause:
Could not create the user manager MBean.

Action:
Check errors in log files and contact the domain administrator.

JPS-05501
Cannot create the role manager MBean.

Category:
Configuration

Cause:
Could not create the role manager MBean.

Action:
Check the log files for errors and contact domain administrator.

JPS-05502
Cannot create the identity store MBean.

Category:
Configuration

Cause:
Could not create the identity store MBean.

Action:
Check log files and contact the domain administrator.

JPS-05513
Failed to determine realms to migrate file {0}. Reason {1}.

Category:
Programmatic

Cause:
Failed determine realms to migrate file {0}. Reason {1}.

Action:
Check log files and try again.

JPS-05521
Invalid jaas.login.controlFlag {0} found for {1} service instance. Valid values should be {2}.

Category:
Requests/Responses

Cause:
Invalid jaas.login.controlFlag {0} found for {1} service instance. Valid values should be {2}.

Action:
Use a valid value.

JPS-05542
Bootstrap credential store context missing

Category:
Compliance

Cause:
Could not find bootstrap credstore context

Action:
Contact aystem administrator

JPS-05546
Bootstrap credential store service missing

Category:
Compliance

Cause:
Could not find bootstrap credstore service

Action:
Contact system administrator

JPS-05626
Bootstrap credential already present in store

Category:
Compliance

Cause:
Credential already present in the store

Action:
use different map name or key name for the credential

JPS-05657
Bootstrap credential store context {0} missing

Category:
Compliance

Cause:
Could not find bootstrap credential store context

Action:
Contact aystem administrator

JPS-05658
Bootstrap credential store service {0} missing from bootstrap credential store context {1}

Category:
Compliance

Cause:
Could not find bootstrap credential store service

Action:
Contact system administrator

JPS-05659
location attribute missing from bootstrap credential store service {0}

Category:
Compliance

Cause:
Could not find location attribute of bootstrap credential store service

Action:
Contact system administrator

JPS-06000
The source context {0} is missing in jps configuration file.

Category:
Configuration

Cause:
While migrating a security store, found that the context, specified as source {0}, did not exist in jps-config.xml.

Action:
Provide a context for source that is present in jps-config.xml.

JPS-06001
The destination context {0} is missing in jps configuration file.

Category:
Configuration

Cause:
While migration of a security store, found that the context, specified as destination {0}, did not exist in jps-config.xml.

Action:
Provide a context for destination that is present in jps-config.xml.

JPS-06002
Cannot clean the destination credential store. Reason {0}.

Category:
Upgrade

Cause:
A codebase grant was found without the required permissions.

Action:
Set the right permissions to the codebase grant.

JPS-06003
Cannot migrate credential folder/key {0}/{1}.Reason {2}.

Category:
Upgrade

Cause:
Cannot migrate this credential.

Action:
Verify that the credential is correctly specified.

JPS-06004
Cannot migrate an unknown user. Reason {0}.

Category:
Upgrade

Cause:
Cannot migrate this user.

Action:
Verify that the user is correctly specified.

JPS-06005
Cannot get password of user {0}. Reason {1}.

Category:
Upgrade

Cause:
Cannot get this user password.

Action:
Verify that the password is correctly specified.

JPS-06006
Cannot migrate user {0}. Reason {1}.

Category:
Upgrade

Cause:
Cannot migrate this user name.

Action:
Verify that the user name is correctly specified.

JPS-06007
Cannot migrate an unknown role. Reason {0}.

Category:
Upgrade

Cause:
Cannot migrate this role.

Action:
Verify that the role is correctly specified.

JPS-06008
Cannot migrate role {0}. Reason {1}.

Category:
Upgrade

Cause:
Cannot migrate this role name.

Action:
Verify that the role name is correctly specified.

JPS-06009
Cannot migrate any member of role {0}. Reason {1}.

Category:
Upgrade

Cause:
Cannot migrate members.

Action:
Verify that the members are correctly specified.

JPS-06010
Cannot migrate an unknown member of role {0}. Reason {1}.

Category:
Upgrade

Cause:
Cannot migrate this member.

Action:
Verify that the member is correctly specified.

JPS-06011
Cannot migrate member {0} of role: {1}. Reason {2}.

Category:
Upgrade

Cause:
Cannot migrate this member name.

Action:
Verify that the member name is correctly specified.

JPS-06012
Cannot migrate a global grant. Reason {0}.

Category:
Upgrade

Cause:
Could not migrate a global grant. Reason {0}.

Action:
Verify that the grant is correctly specified.

JPS-06013
Cannot migrate an application grant. Reason {0}.

Category:
Upgrade

Cause:
Could not migrate an application grant. Reason {0}.

Action:
Verify that the application grant is correctly specified.

JPS-06014
Cannot migrate an indirect password for {0}. Reason {1}.

Category:
Upgrade

Cause:
Could not migrate an indirect password due to an exception.

Action:
Verify that the indirect password is correctly specified.

JPS-06015
Cannot migrate an indirect password for {0} because the specified realm is null.

Category:
Upgrade

Cause:
Could not migrate an indirect password because the given realm was null.

Action:
Provide a non-null realm.

JPS-06016
Cannot migrate an indirect password for {0} because the specified user name is null.

Category:
Upgrade

Cause:
Could not migrate an indirect password because the given user name was null.

Action:
Provide a non-null user name.

JPS-06017
Cannot migrate an indirect password for {0} because the specified realm does not exist.

Category:
Upgrade

Cause:
Could not migrate an indirect password because the input realm does not exist.

Action:
Provide an existing realm.

JPS-06018
Cannot migrate an indirect password for {0} because the specified user does not exist.

Category:
Upgrade

Cause:
Could not migrate an indirect password because the input user does not exist.

Action:
Provide an existing user.

JPS-06019
The identity store associated with context {0} is missing in jps-config.xml.

Category:
Configuration

Cause:
While migration of a policy store, found that the context, specified as containing the associated identity store {0}, did not exist in jps-config.xml.

Action:
Provide a context to associate identity store that is present in jps-config.xml.

JPS-06020
The principal class {0} specified in the source policy store cannot be loaded. Reason {1}.

Category:
Upgrade

Cause:
Could not load a class. Reason {0}.

Action:
Ensure the class is in the class path.

JPS-06021
Cannot migrate the credentials in the folder {0}. Reason: {1}.

Category:
Upgrade

Cause:
Cannot migrate the credentials in this folder.

Action:
Check the folder in the source credential store.

JPS-06022
Cannot determine the folder to be migrated.

Category:
Upgrade

Cause:
The credential store has more than one folder and the folder to be migrated was not defined.

Action:
Specify the folder to be migrated.

JPS-06023
The input file {0} specified for migration or upgrade is not valid.

Category:
Upgrade

Cause:
The file {0} was non-readable, empty, or did not exist.

Action:
Provide a valid file.

JPS-06024
Cannot initialize the destination identity store.

Category:
Upgrade

Cause:
One or more required configuration properties were not be properly defined.

Action:
Check the configuration of the destination identity store.

JPS-06025
There are undefined credential properties for the destination identity store.

Category:
Upgrade

Cause:
One or more required configuration properties for credentials were not defined.

Action:
Check the configuration of the destination identity store.

JPS-06026
Cannot get credentials for the destination identity store from the domain credential store.

Category:
Upgrade

Cause:
Credentials were not found in the domain credential store.

Action:
Ensure that the domain credential store has the appropriate credentials.

JPS-06027
Cannot migrate the specified realm.

Category:
Upgrade

Cause:
The specified realm was not found in the source store.

Action:
Specify a valid realm name.

JPS-06028
The required identity store property {0} required for migration is undefined.

Category:
Other

Cause:
A property required for migration was not configured in the identity store.

Action:
Specify the missing configuration property.

JPS-06029
JAZN properties cannot be read from config file {0}.

Category:
Upgrade

Cause:
JAZN properties could not be read from config file {0}.

Action:
Check the configuration file and try again.

JPS-06030
The required JAZN property {0} could not be read.

Category:
Upgrade

Cause:
A required JAZN property {0} could not be read.

Action:
Check the configuration file and try again.

JPS-06031
No application is configured in the source policy store.

Category:
Upgrade

Cause:
No application was configured in the source policy store.

Action:
Check the source policy store.

JPS-06032
Unable to determine the application policy to migrate.

Category:
Upgrade

Cause:
More than one application was configured in the source policy store.

Action:
Check the source policy store.

JPS-06033
The source credential store contains no credentials.

Category:
Requests/Responses

Cause:
The requested credential was not found in the credential store.

Action:
Ensure that the credential store has the requested credential.

JPS-06034
The folder {0} is missing in the credential store.

Category:
Requests/Responses

Cause:
The requested map name was not found in the credential store.

Action:
Ensure that the credential store contains the requested map name.

JPS-06035
The destination file {0} already exists; the existing LDIF file will not be appended or overwritten.

Category:
Requests/Responses

Cause:
The destination file is already present.

Action:
Delete the destination file, or provide the name of a non-existing file.

JPS-06036
Cannot determine the default realm to migrate file {0}. Reason {1}.

Category:
Programmatic

Cause:
An internal error occurred while determining the default realm.

Action:
Check log files and try again.

JPS-06037
Cannot initialize the source credential store.

Category:
Upgrade

Cause:
The configuration for the credential store was invalid.

Action:
Verify that the credential store configuration is correct and try again.

JPS-06038
Cannot initialize the destination credential store.

Category:
Upgrade

Cause:
The configuration for the credential store was invalid.

Action:
Verify that the credential store configuration is correct and try again.

JPS-06039
Cannot migrate property {0} of user {1}. Reason {2}.

Category:
Upgrade

Cause:
Cannot migrate property {0} for user {1}. Reason {2}.

Action:
Check the log files and retry migrating.

JPS-06040
Cannot migrate property {0} of role {1}. Reason {2}.

Category:
Upgrade

Cause:
Cannot migrate property {0} for role {1}. Reason {2}.

Action:
Check the log files and retry migrating.

JPS-06041
The switch or keyword " {0} " is not applicable to " {1} = {2} ".

Category:
Requests/Responses

Cause:
One or more optional switches or keywords were invalid.

Action:
Refer to the command documentation for the correct usage.

JPS-06042
Invalid scope for migration.

Category:
Requests/Responses

Cause:
Value of scope keyword was invalid.

Action:
Enter only one of the defined values/alias of scope as a value for the keyword scope.

JPS-06043
The source application is undefined but required to migrate application-specific policies.

Category:
Requests/Responses

Cause:
Optional keyword srcApp was not defined.

Action:
Specify, in the parameter srcApp, the value of the application whose policies are to be migrated.

JPS-06044
Cannot create the temporary file {0}.

Category:
Programmatic

Cause:
Could not write the XML file.

Action:
Check permissions or disk space in the java.io.tmpdir directory.

JPS-06045
Cannot parse the file {0}.

Category:
Programmatic

Cause:
Could not parse the XML file.

Action:
Check that the file is present in the java.io.tmpdir directory, and that it contains well-formed XML.

JPS-06046
Cannot delete the file {0}.

Category:
Programmatic

Cause:
The temp file could not be deleted.

Action:
Check that the file is not being accessed by other applications.

JPS-06047
Cannot migrate user credentials of user {0}.

Category:
Configuration

Cause:
The source identity store was configured not to give cleartext password.

Action:
Configure the source identity store to obfuscate password.

JPS-06048
Null values passed in for username or application stripes.

Category:
Programmatic

Cause:
The user name or the application stripe was null.

Action:
The user name must not be null. The list of application names must be null if only global policies are to be extracted.

JPS-06049
Application list is empty. Only global policies will be extracted.

Category:
Programmatic

Cause:
The list of applications was empty.

Action:
Only global policies are collected.

JPS-06050
file {0} was not found

Category:
Programmatic

Cause:
The xml file was not found.

Action:
Check if the file is present in the java.io.tmpdir directory.

JPS-06051
Processing of privilege roles is supported only when migrating an XML Policy store to an LDAP Policy Store.

Category:
Upgrade

Cause:
Processing of privilege roles was supported only when migrating an XML policy store to an LDAP policy store.

Action:
Make sure that the source store is XML-based and the destination store is LDAP-based.

JPS-06052
Error while processing a PermissionSet grant.

Category:
Upgrade

Cause:
Error encountered while processing permissionSet grant.

Action:
Check log files for details.

JPS-06053
Processing privilege roles failed. Cause {0}

Category:
Upgrade

Cause:
The processing of privilege roles failed.

Action:
Check log files for detials.

JPS-06054
Error in creating resourceTypes in destination store. Cause {0}

Category:
Upgrade

Cause:
Error encountered while creating resourceTypes in destination store.

Action:
Check log files for detials.

JPS-06055
Location of the ldif file containing resourceType definitions cannot be null.

Category:
Upgrade

Cause:
Location of the LDIF file containing resourceType definitions was null or not found.

Action:
Provide the absolute path for the resource file.

JPS-06056
Error while reading resource type file {0}.

Category:
Upgrade

Cause:
Error encountered while reading the resource type file {0}.

Action:
Ensure that the file exists and that it has the expected format.

JPS-06057
Resource type name or matcher class cannot be null.

Category:
Upgrade

Cause:
Resource type name or matcher class was null.

Action:
Provide a valid name and matcher class for the resource type.

JPS-06058
Permission class {0} with more than one matching resource type found.

Category:
Upgrade

Cause:
Permission class had more than one matching resource type.

Action:
Ensure that the a permission class has just one matching resource type.

JPS-06059
A grant entry containing {0} as one of principals has multiple principal entries. This entry cannot be processed.

Category:
Upgrade

Cause:
A grant for a privilege role had multiple principals.

Action:
Ensure that the privilege role grant has a single principal.

JPS-06060
The resource type definition file is missing.

Category:
Upgrade

Cause:
The resource type definition file was not found.

Action:
Provide the absolute path location for the resource definition file in LDIF format when using the option procPrivOption.

JPS-06061
The switch or keyword " {0} " is not defined for " {1} = {2} ".

Category:
Requests/Responses

Cause:
One or more optional switches or keywords were invalid.

Action:
Refer to the command documentation for the correct usage.

JPS-06062
Application role {0} corresponding to a member application role not defined.

Category:
Upgrade

Cause:
Application role not defined.

Action:
Check logs for detials.

JPS-06063
No Matching resource type definition found for permission class {0}.

Category:
Upgrade

Cause:
Permission class representing resource granted to a privilleged role does not have corresponding resource type definition.

Action:
Make sure a permission class has one matching resource type.

JPS-06064
Error getting the application role {0} from the source policy store

Category:
Upgrade

Cause:
The application role was either not present or defined multiple times.

Action:
Check the source policy store and make sure that the application role is uniquely defined.

JPS-06065
Report generation failed

Category:
Configuration

Cause:
.

Action:
.

JPS-06066
Invalid value for mode: {0}.

Category:
Security

Cause:
Invalid value for mode: {0}.

Action:
Make sure the value for mode is valid

JPS-06067
{0} config file either not found or not a valid file.

Category:
Upgrade

Cause:
{0} config file either not found or not a valid file

Action:
Make sure to provide a valid config file

JPS-06068
Unable to read configurations from jazn config file : {0}.

Category:
Upgrade

Cause:
Unable to read configurations from jazn data file : {0}.

Action:
Check the jazn data file.

JPS-06069
Provider referred from jazn config file {0} is of type XML and not LDAP.

Category:
Upgrade

Cause:
Provider referred from jps-config file {0} is of type XML and not LDAP.

Action:
Refer to a provider of type LDAP.

JPS-06070
Unable to read policies from policy store.

Category:
Upgrade

Cause:
Unable to read policies from policy store.

Action:
Check the policy store.

JPS-06071
Unable to read global policies from policy store.

Category:
Upgrade

Cause:
Unable to read global policies from policy store.

Action:
Check the policy store.

JPS-06072
Unable to read permissions for grantee {0} from policy store.

Category:
Upgrade

Cause:
Unable to read permissions for grantee {0} from policy store.

Action:
Check the policy store.

JPS-06073
Unable to read realm policies from policy store.

Category:
Upgrade

Cause:
Unable to read realm policies from policy store.

Action:
Check the policy store.

JPS-06074
Unable to read realm policies from realm {0} from policy store.

Category:
Upgrade

Cause:
Unable to read realm policies from realm {0} from policy store.

Action:
Check the policy store.

JPS-06075
Unsupported resource type file format. Use either an ldif file or a jazn-data with only resource type definitions.

Category:
Upgrade

Cause:
Unsupported resource type file format.

Action:
Use either an ldif file or a jazn-data with only resource type definitions.

JPS-06076
A Resource Type referred by {0} is expected to have a matching class {1} but has {2}.

Category:
Upgrade

Cause:
A Resource Type referred by a Permission is expected to have the same matching class as defined in the Permission

Action:
Make sure a permission class has one matching resource type with the same class name.

JPS-06077
A Resource Type referred by {0} is not defined.

Category:
Upgrade

Cause:
A Resource Type referred by a Permission is not defined.

Action:
Make sure a permission class has one matching resource type.

JPS-06078
Cannot migrate keystore/stripe {0}/{1}.Reason {2}.

Category:
Upgrade

Cause:
Cannot migrate the keystore in this stripe.

Action:
Check the keystore and stripe in the source keystore service.

JPS-06079
Cannot determine the stripe to be migrated.

Category:
Upgrade

Cause:
The keystore service has more than one stripes and the stripe to be migrated was not defined.

Action:
Specify the stripe to be migrated.

JPS-06080
The source keystore service contains no keystore within the given application stripe.

Category:
Requests/Responses

Cause:
The requested keystore was not found in the keystore service.

Action:
Ensure that the keystore service has the requested keystore.

JPS-06082
Cannot initialize the source keystore service.

Category:
Upgrade

Cause:
The configuration for the keystore service was invalid.

Action:
Verify that the keystore service configuration is correct and try again.

JPS-06083
Cannot initialize the destination keystore service.

Category:
Upgrade

Cause:
The configuration for the keystore service was invalid.

Action:
Verify that the keystore service configuration is correct and try again.

JPS-06084
Cannot clean the destination keystore service. Reason {0}.

Category:
Upgrade

Cause:
A codebase grant was found without the required permissions.

Action:
Set the right permissions to the codebase grant.

JPS-06085
Resource types not defined for the application {0}.

Category:
Upgrade

Cause:
Resource Types not found for the application {0}.

Action:
Define the resource types for the application {0}.

JPS-06086
Cannot upgrade policies for application {0}.

Category:
Upgrade

Cause:
Exception during policy upgradation.

Action:
Check the Causing exception and fix the error.

JPS-06087
Duplicate permissions: {0} present in grant in source.

Category:
Upgrade

Cause:
Duplicate permissions are present in a grant in source.

Action:
See error message.

JPS-06088
Duplicates principals:{0} present in grant in source.

Category:
Upgrade

Cause:
Duplicates principals are present in a grant in source.

Action:
See error message.

JPS-06089
Duplicate grant {0} present in source.

Category:
Upgrade

Cause:
Duplicate grants are present in source.

Action:
See error message.

JPS-06090
Duplicate app-role {0} present in source.

Category:
Upgrade

Cause:
Duplicate app-roles are present in source.

Action:
See error message.

JPS-06091
Duplicate member {0} present in an app-role in source.

Category:
Upgrade

Cause:
Duplicate members are present in an app-role in source.

Action:
See error message.

JPS-06092
Can not overwrite global policy.

Category:
Upgrade

Cause:
Can not overwrite global policy.

Action:
Do not set overwrite to true

JPS-06100
Policy Store version {0} and Oracle Platform Security Services Version {1} are not compatible.

Category:
Security

Cause:
The policy store version and the version of Oracle Platform Security Services does not match

Action:
Upgrade your binaries or your policy store.

JPS-06101
Cannot initialize the source auditstore service.

Category:
Upgrade

Cause:
The configuration for the audit store was invalid.

Action:
Verify that the audit store configuration is correct and try again.

JPS-06102
Cannot initialize the destination auditstore service.

Category:
Upgrade

Cause:
The configuration for the audit store was invalid.

Action:
Verify that the audit store configuration is correct and try again.

JPS-06103
Default Admin Role {0} not found in the policy domain {1} in the destination policy store

Category:
Security

Cause:
The destination policy store may not conform to leates version and need to be upgraded

Action:
See error message.

JPS-06104
Default Admin Role {0} not found in the application {1} in the destination policy store

Category:
Security

Cause:
The destination policy store may not conform to leates version and need to be upgraded

Action:
See error message.

JPS-06105
Default system Admin Role {0} not found in the destination policy store

Category:
Security

Cause:
The destination policy store may not conform to leates version and need to be upgraded

Action:
See error message.

JPS-06106
Instantiation of bootstrap credential store specified in file {0} failed. Reason {1}

Category:
Requests/Responses

Cause:
The configuration provided is not valid.

Action:
Provide a valid configuration file which has configuration for bootstrap credential.

JPS-06107
Instantiation of credential store at path {0} failed. Reason: {1}

Category:
Requests/Responses

Cause:
An underlying exception prevented initialization of credentials file.

Action:
Check the cause of the exception and fix it.

JPS-06108
Import/Export of keys failed. Reason: {0}

Category:
Requests/Responses

Cause:
An underlying exception prevented exporting/importing of key.

Action:
Check the cause of the exception and fix it.

JPS-06109
Cannot read key from key file in Directory {0}. Reason {1}.

Category:
Requests/Responses

Cause:
An underlying exception prevented reading of key.

Action:
Check the cause of the exception and fix it.

JPS-06110
Key file Directory {0} does not have write permissions.

Category:
Requests/Responses

Cause:
Key file directory not writable.

Action:
Change the permissions of the directory.

JPS-06111
Key file Directory {0} does not have read permissions.

Category:
Requests/Responses

Cause:
Key file directory is not readable.

Action:
Change the permissions of the directory.

JPS-06112
Key file Directory {0} does not exist.

Category:
Requests/Responses

Cause:
The path specified either donnot exist or is not a directory.

Action:
Provide a valid directory.

JPS-06113
Configuration file {0} is not valid. It is either not present or does not have read permissions.}

Category:
Requests/Responses

Cause:
The file is either not present or is not readable.

Action:
Provide a valid file.

JPS-06114
Key is not present in the key file in Directory {0}.

Category:
Requests/Responses

Cause:
Export might have not completed successfully.

Action:
Provide key file that has key in it.

JPS-06115
Empty DB username information. Please make sure to provide the correct jdbcUser info.

Category:
Requests/Responses

Cause:
Empty DB username information.

Action:
Please make sure to provide the correct jdbcUser info.

JPS-06116
Empty DB password information. Please make sure to provide the correct jdbcPassword info.

Category:
Requests/Responses

Cause:
Empty DB password information.

Action:
Please make sure to provide the correct jdbcPassword info.

JPS-06117
Empty JDBC host and port information. Please make sure to provide the correct jdbcUrl info.

Category:
Requests/Responses

Cause:
Empty DB host and port information.

Action:
Please make sure to provide the correct jdbcUrl info.

JPS-06118
Empty JDBC Driver information. Please make sure to provide the correct jdbcDriver info.

Category:
Requests/Responses

Cause:
Empty JDBC Driver information.

Action:
Please make sure to provide the correct jdbcDriver info.

JPS-06119
Recovery failed. Key backup not Found.

Category:
Requests/Responses

Cause:
No import was performed or import was not sucessfull.

Action:
import the key(s) again.

JPS-06120
Policystore is already upgraded, so it will not be upgraded again.

Category:
Upgrade

Cause:
Policystore is already upgraded.

Action:
Policystore will not be upgraded again.

JPS-06121
Keystore is already upgraded, so it will not be upgraded again.

Category:
Upgrade

Cause:
Keystore is already upgraded.

Action:
Keystore will not be upgraded again.

JPS-06122
Auditstore is already upgraded, so it will not be upgraded again.

Category:
Upgrade

Cause:
Auditstore is already upgraded.

Action:
Auditstore will not be upgraded again.

JPS-06123
XACML Policy/PolicySet Defaults not supported in OES.

Category:
Programmatic

Cause:
XACML Policy/PolicySet Defaults not supported in OES.

Action:
XACML Policy/PolicySet Defaults not supported in OES.

JPS-06124
XACML Policy/PolicySet Max Delegation Depth not supported in OES.

Category:
Programmatic

Cause:
XACML Policy/PolicySet Max Delegation Depth not supported in OES.

Action:
XACML Policy/PolicySet Max Delegation Depth not supported in OES.

JPS-06125
XACML attribute Issuer not supported in OES for the element {0}.

Category:
Programmatic

Cause:
XACML attribute Issuer not supported in OES.

Action:
XACML attribute Issuer not supported in OES.

JPS-06126
XACML PolicySet/Policy/Rule Combiner Parameters not supported in OES.

Category:
Programmatic

Cause:
XACML Policy/Rule Combiner Parameters not supported in OES.

Action:
XACML Policy/Rule Combiner Parameters not supported in OES.

JPS-06127
XACML Attribute Selector not supported in OES.

Category:
Programmatic

Cause:
XACML Attribute Selector not supported in OES.

Action:
XACML Attribute Selector not supported in OES.

JPS-06128
Unknown Policy/PolicySet Id reference {0}.

Category:
Programmatic

Cause:
Unknown Variable reference.

Action:
Provide an Id Reference of a Policy/PolicySet that exists in the application

JPS-06129
Unknown Variable reference {0}.

Category:
Programmatic

Cause:
Unknown Policy/PolicySet Id reference.

Action:
Provide a variable Reference for which a vadiable definition exists in the policy

JPS-06131
Migration of Audit Store data in progress.....

Category:
Upgrade

Cause:

Action:

JPS-06132
Migration of Audit Store data completed, Time taken for migration is {0}

Category:
Upgrade

Cause:
Migration of Audit Store data completed, Time taken for migration is {0}.

Action:
No actions are required.

JPS-06133
Migration of Credential Store data in progress.....

Category:
Upgrade

Cause:

Action:

JPS-06134
Migration of Credential Store data completed, Time taken for migration is {0}

Category:
Upgrade

Cause:
Migration of Credential Store data completed, Time taken for migration is {0}.

Action:
No actions are required.

JPS-06135
Migration of Credential folder data in progress.....

Category:
Upgrade

Cause:

Action:

JPS-06136
Migration of Credential folder data completed, Time taken for migration is {0}

Category:
Upgrade

Cause:
Migration of Credential folder data completed, Time taken for migration is {0}.

Action:
No actions are required.

JPS-06137
Migration of Application Policies {0} in progress.....

Category:
Upgrade

Cause:

Action:

JPS-06138
Migration of Application Policies {0} completed, Time taken for migration is {1}

Category:
Upgrade

Cause:
Migration of Application Policies {0} completed, Time taken for migration is {1}.

Action:
No actions are required.

JPS-06139
Migration of Global Policies in progress.....

Category:
Upgrade

Cause:

Action:

JPS-06140
Migration of Global Policies completed, Time taken for migration is {0}

Category:
Upgrade

Cause:
Migration of System Policies completed, Time taken for migration is {0}.

Action:
No actions are required.

JPS-06141
Migration of All[Application + Global] policies in progress.....

Category:
Upgrade

Cause:

Action:

JPS-06142
Migration of All[Application + Global] policies completed, Time taken for migration is {0}

Category:
Upgrade

Cause:
Migration of All[Application + Global] policies completed, Time taken for migration is {0}.

Action:
No actions are required.

JPS-06143
Migration of Java Policies in progress.....

Category:
Upgrade

Cause:

Action:

JPS-06144
Migration of Java Policies completed, Time taken for migration is {0}

Category:
Upgrade

Cause:
Migration of Java Policies completed, Time taken for migration is {0}.

Action:
No actions are required.

JPS-06145
Migration of Identity Store data in progress.....

Category:
Upgrade

Cause:

Action:

JPS-06146
Migration of Identity Store data completed, Time taken for migration is {0}

Category:
Upgrade

Cause:
Migration of Identity Store data completed, Time taken for migration is {0}.

Action:
No actions are required.

JPS-06147
Migration of Admin Role Members started

Category:
Upgrade

Cause:

Action:

JPS-06148
Migration of {0} Admin Role Members completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Admin Role Members completed in {1}.

Action:
No actions are required.

JPS-06149
Migration of Grants started

Category:
Upgrade

Cause:

Action:

JPS-06150
Migration of {0} Grants completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Grants completed in {1}.

Action:
No actions are required.

JPS-06151
Migration of Policy Domains started

Category:
Upgrade

Cause:

Action:

JPS-06152
Migration of {0} Policy Domains completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Policy Domains completed in {1}.

Action:
No actions are required.

JPS-06153
Migration of Application Roles started

Category:
Upgrade

Cause:

Action:

JPS-06154
Migration of {0} Application Roles completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Application Roles completed in {1}.

Action:
No actions are required.

JPS-06155
Migration of Resources started

Category:
Upgrade

Cause:

Action:

JPS-06156
Migration of {0} Resources completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Resources completed in {1}.

Action:
No actions are required.

JPS-06157
Migration of Admin Roles started

Category:
Upgrade

Cause:

Action:

JPS-06158
Migration of {0} Admin Roles completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Admin Roles completed in {1}.

Action:
No actions are required.

JPS-06159
Migration of Policies started

Category:
Upgrade

Cause:

Action:

JPS-06160
Migration of {0} Policies completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Policies completed in {1}.

Action:
No actions are required.

JPS-06161
Migration of Resource Types started

Category:
Upgrade

Cause:

Action:

JPS-06162
Migration of {0} Resource Types completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Resource Types completed in {1}.

Action:
No actions are required.

JPS-06163
Migration of Permission Sets started

Category:
Upgrade

Cause:

Action:

JPS-06164
Migration of {0} Permission Sets completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Permission Sets completed in {1}.

Action:
No actions are required.

JPS-06165
Migration of Functions started

Category:
Upgrade

Cause:

Action:

JPS-06166
Migration of {0} Functions completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Functions completed in {1}.

Action:
No actions are required.

JPS-06167
Migration of Attributes started

Category:
Upgrade

Cause:

Action:

JPS-06168
Migration of {0} Attributes completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Attributes completed in {1}.

Action:
No actions are required.

JPS-06169
Migration of Role Policies started

Category:
Upgrade

Cause:

Action:

JPS-06170
Migration of {0} Role Policies completed in {1}

Category:
Upgrade

Cause:
Migration of {0} Role Policies completed in {1}.

Action:
No actions are required.

JPS-06171
Failed to create policy store object, please check the logs.

Category:
Upgrade

Cause:
Failed to create policy store object, please check the logs.

Action:
Please check the logs.

JPS-06172
{0} service not found in default context, skipping upgrade for this service.

Category:
Upgrade

Cause:
{0} service not found in default context of OPSS configuration

Action:
Configure {0} service in default context of OPSS configuration files and run the upgrade again

JPS-06173
Policystore upgrade from {0} to {1} not supported

Category:
Upgrade

Cause:
Policystore upgrade from {0} to {1} not supported

Action:
Policystore must be upgraded to a higher patchset first.

JPS-06174
OPSS data is not backed up as part of upgrade process in LDAP/DB based OPSS Store

Category:
Upgrade

Cause:
OPSS data is not backed up as part of upgrade process in LDAP/DB based OPSS Store

Action:
Back up data manually before running upgrade in LDAP/DB based OPSS Store.

JPS-06175
Migration of CombiningAlgorithms started

Category:
Upgrade

Cause:

Action:

JPS-06176
Migration of {0} CombiningAlgorithms completed in {1}

Category:
Upgrade

Cause:

Action:

JPS-06177
Migration of Policy Rule started

Category:
Upgrade

Cause:

Action:

JPS-06178
Migration of {0} Policy Rule completed in {1}

Category:
Upgrade

Cause:

Action:

JPS-06179
Migration of Policy Set started

Category:
Upgrade

Cause:

Action:

JPS-06180
Migration of {0} Policy Set completed in {1}

Category:
Upgrade

Cause:

Action:

JPS-06181
Migration of Key Store data in progress.....

Category:
Upgrade

Cause:

Action:

JPS-06182
Migration of Key Store data completed, Time taken for migration is {0}

Category:
Upgrade

Cause:
Migration of Key Store data completed, Time taken for migration is {0}.

Action:
No actions are required.

JPS-06183
Migration of Key Store stripe data in progress.....

Category:
Upgrade

Cause:

Action:

JPS-06184
Migration of Key Store stripe data completed, Time taken for migration is {0}

Category:
Upgrade

Cause:
Migration of KeyStore stripe data completed, Time taken for migration is {0}.

Action:
No actions are required.

JPS-06185
More than one properties set references present for policy store service instance in jps-config file {0}

Category:
Requests/Responses

Cause:
More than one property set references present in policy store service instance in jps-config.xml file

Action:
Make sure only one property set references under policy store service instance in jps-config.xml file

JPS-06186
Either bootstrap credstore or key store service instance is not found in bootstrap context

Category:
Requests/Responses

Cause:
Either bootstrap credstore or key store service instance is not found in bootstrap context

Action:
Ensure both bootstrap credstore and keystore service instance reference in bootstrap context is present

JPS-06187
Not able to find file based keystore service instance, while adding keystore service instance to bootstrap context

Category:
Requests/Responses

Cause:
Not able to find file based keystore service instance, while adding keystore service instance to bootstrap context

Action:
Ensure file based keystore service instance reference in jps-config.xml is present

JPS-06188
New Application Policy {0} created during migration

Category:
Upgrade

Cause:
Migration of Application Roles completed in {0}.

Action:
No actions are required.

JPS-06189
Migrate Permission Name = {0}, Exception during modification of permission. Message = {1}.

Category:
Upgrade

Cause:
Migrate Permission Name = {0}, Exception during modification of permission. Message = {1}.

Action:
No actions are required.

JPS-06190
Miagrtion failed in Perm Member : {0}.

Category:
Upgrade

Cause:
Miagrtion failed in Perm Member : {0}

Action:
No actions are required.

JPS-06191
PermissionMigrator Thread {0} failed due to {1}.

Category:
Upgrade

Cause:
PermissionMigrator Thread {0} failed due to {1}.

Action:
No actions are required.

JPS-06192
Cannot get source policy store.

Category:
Configuration

Cause:
While migrating a security store, cannot get source policy store.

Action:
Check and make sure source policy store is configured correctly.

JPS-06193
Cannot get destination policy store.

Category:
Configuration

Cause:
While migrating a security store, cannot get destionation policy store.

Action:
Check and make sure destination policy store is configured correctly.

JPS-06194
There are multiple logic security stores in the db schema : {0}. Please split them before doing upgrade.

Category:
Upgrade

Cause:
Found multiple security stores in the db schema.

Action:
Reassociate each security store to separated db schema.

JPS-06195
Security store is already transformed, so it will not be transformed again.

Category:
Upgrade

Cause:
Security store is already transformed.

Action:
Security store will not be transfromed again.

JPS-06196
Transformation of security store started.

Category:
Upgrade

Cause:
Begin security store transformation.

Action:
No actions are required.

JPS-06197
Transformation of security store completed in {0}.

Category:
Upgrade

Cause:
Finish security store transformation.

Action:
No actions are required.

JPS-06198
OPSS Schema is not upgraded. Current schema version is {0}. Schema version for upgrade is {1}

Category:
Upgrade

Cause:
OPSS Schema is not upgraded.

Action:
Upgrade OPSS Schema first before upgrading Opss Data and Config.

JPS-06199
Source application type dose not match the type of destination application.

Category:
Upgrade

Cause:
Source application type dose not match the destination application type.

Action:
No actions are required.

JPS-06200
Property {0} with value "{1}" is invalid in the meta data property file.

Category:
Security

Cause:
Property {0} with value "{1}" is invalid in the meta data property file.

Action:
Check the meta data property file.

JPS-06201
Property {0} is missing in the meta data property file.

Category:
Security

Cause:
Property {0} is missing in the meta data property file.

Action:
Check the meta data property file.

JPS-06202
Cannot migrate {0} named "{1}", policy object already exists in application policy with different metadata.

Category:
Programmatic

Cause:
{0} named "{1}" already exists in application policy with differnt metadata.

Action:
Check policy store data in source application policy, remove conflict data.

JPS-06500
Alias already exists in the keystore

Category:
Configuration

Cause:
The specified alias name already existed in the keystore.

Action:
Specify a unique alias name.

JPS-06501
Keystore {0} in stripe {1} already exists

Category:
Configuration

Cause:
Keystore with the given name already existed.

Action:
Specify a unique keystore name.

JPS-06502
Failed to read keystore. Reason {0}

Category:
Configuration

Cause:
Could not read the keystore.

Action:
Verify the keystore location and that sufficient permissions are in place.

JPS-06503
Failed to write keystore. Reason {0}

Category:
Configuration

Cause:
Could not read the keystore.

Action:
Verify the keystore location, that sufficient permissions are in place and that sufficient disk space is available.

JPS-06504
Failed to perform cryptographic operation

Category:
Configuration

Cause:
The java provider did not support this cryptographic operation.

Action:
Verify that a provider that supports this algorithm/padding/key is configured.

JPS-06505
Failed to generate certificate request

Category:
Compliance

Cause:

Action:

JPS-06506
Key generation algorithm not supported

Category:
Configuration

Cause:
An unsupported key-pair generation algorithm was used.

Action:
Specify a supported key-pair generation algorithm.

JPS-06507
Root CA import failed.

Category:
Configuration

Cause:
The root CA certificate and/or key file was malformed.

Action:
Verify that the root CA certificate and/or key files is valid.

JPS-06508
Failed to generate CA signed certificate.

Category:
Compliance

Cause:

Action:

JPS-06509
The keystore has been moved or deleted.

Category:
Configuration

Cause:
The keystore did not exist at this location.

Action:
Verify that the location of keystore is correct.

JPS-06510
The keystore location property is not configured, or the configured value {0} is invalid.

Category:
Configuration

Cause:
The keystore location was not specified.

Action:
Check the value of the location attribute.

JPS-06511
Cannot create keystore at {0}.

Category:
Configuration

Cause:
Could not create the keystore.

Action:
Verify the store location, that sufficient permissions are in place, and that sufficient disk space is available.

JPS-06513
Failed to save keystore. Reason :

Category:
Compliance

Cause:

Action:

JPS-06514
Opening of file based keystore failed. Reason :

Category:
Compliance

Cause:
Keystore could not be opened

Action:
Contact system administrator

JPS-06515
Refreshing of file based keystore failed. Reason {0}

Category:
Compliance

Cause:
Refresh of keystore failed

Action:
Contact system administrator

JPS-06516
Failed to get credential store. Reason {0}

Category:
Compliance

Cause:
Could not get credential store.

Action:
Verify credential store is correctly configured and initialized.

JPS-06517
Failed to create the keystore {0} in stripe {1}.

Category:
Compliance

Cause:

Action:

JPS-06518
Keystore {0} in stripe {1} does not exist.

Category:
Configuration

Cause:
Could not perform this operation since the keystore did not exist.

Action:
Specify an existing keystore name for this operation.

JPS-06519
Failed to get/set credential with map {0} and key {1} in bootstrap credstore. Reason {2}

Category:
Configuration

Cause:
Credential store was not available or permissions were not in place.

Action:
Verify credential store is correctly configured and permissions are granted.

JPS-06520
Failed to encode/decode certificate or public key.

Category:
Compliance

Cause:

Action:

JPS-06521
Invalid admin password, operation not permitted

Category:
Configuration

Cause:
Invalid admin password was specified.

Action:
Specify the correct admin password to perform this operation.

JPS-06522
Failed to roll over keystore master key.

Category:
Compliance

Cause:

Action:

JPS-06523
Failed to reset keystore administrator password.

Category:
Compliance

Cause:

Action:

JPS-06524
Failed to read certificates from keystore.

Category:
Compliance

Cause:

Action:

JPS-06525
Failed to list/renew expiring certificates.

Category:
Compliance

Cause:

Action:

JPS-06526
Failed to list policy violations in keystore.

Category:
Compliance

Cause:

Action:

JPS-06527
Invalid keystore name {0}.

Category:
Configuration

Cause:
Invalid keystore name was specified.

Action:
Specify a keystore name that is not null or empty and contains only alphanumeric characters.

JPS-06528
Invalid alias value {0}.

Category:
Configuration

Cause:
Invalid alias value was specified.

Action:
Specify an alias value that is not null or empty and contains only alphanumeric characters.

JPS-06529
Passwords must not be null or empty.

Category:
Configuration

Cause:
Password was specified as null or empty.

Action:
Specify a non null or non empty password for a keystore protected by password.

JPS-06530
Invalid stripe value {0}

Category:
Compliance

Cause:

Action:

JPS-06531
Operation failed, keystore password does not match

Category:
Compliance

Cause:

Action:

JPS-06532
Failed to delete the keystore {0} in stripe {1}

Category:
Compliance

Cause:

Action:

JPS-06533
Algorithm {0} not supported

Category:
Configuration

Cause:
The algorithm was not supported by keystore.

Action:
Check the list of supported algorithms and specify one of them.

JPS-06534
Keystore master key roll-over failed.

Category:
Compliance

Cause:

Action:

JPS-06535
Failed to generate secret key with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06536
Failed to import secret key for keystore {0}

Category:
Compliance

Cause:

Action:

JPS-06537
Failed to change password for keystore {0} in stripe {1}

Category:
Compliance

Cause:

Action:

JPS-06538
Cannot set password for trusted certificate entry.

Category:
Compliance

Cause:

Action:

JPS-06539
Operation failed, key password does not match

Category:
Compliance

Cause:

Action:

JPS-06540
Failed to change password for key with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06541
Invalid keystore entry type {0}

Category:
Configuration

Cause:
The keystore entry type was invalid for this operation.

Action:
Check the list of supported keystore entry types from documentation.

JPS-06542
Failed to list aliases for keystore {0} in stripe {1}

Category:
Compliance

Cause:

Action:

JPS-06543
Invalid Distinguished Name {0}

Category:
Compliance

Cause:

Action:

JPS-06544
Failed to generate key pair for alias {0} keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06545
The expected keystore entry with alias "{0}" either does not exist or is not of the specified keystore entry type for keystore "{1}" in stripe "{2}".

Category:
Configuration

Cause:
The alias value either did not exist or did not point to the specified keystore entry type.

Action:
Specify a valid alias value that points to the specified keystore entry type.

JPS-06546
Failed to get secret key with alias {0}

Category:
Compliance

Cause:

Action:

JPS-06547
Failed to get certificate(s) with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06548
Failed to export certificate request for key with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06549
No corresponding key pair found for this certificate

Category:
Configuration

Cause:
The alias value did not point to the matching key pair for this certificate

Action:
Specify a valid alias value that points to a key pair whose public key matches that of the certificate.

JPS-06550
Failed to parse the certificate chain

Category:
Compliance

Cause:

Action:

JPS-06551
Failed to import the key store entry with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06552
Failed to delete the key store entry with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06553
Cannot perform this operation on domain trust store

Category:
Configuration

Cause:
The operation was not supported for domain trust store.

Action:
Check product documentation to see the operations permitted on domain trust store.

JPS-06554
Cannot perform this operation on demo CA keystore

Category:
Compliance

Cause:

Action:

JPS-06555
Mismatch between the values of key aliases and key passwords

Category:
Configuration

Cause:
There should be equal number of entries for key aliases and key passwords

Action:
Ensure that key aliases and key passwords are equal in number.

JPS-06556
Keystore to be imported is not valid

Category:
Configuration

Cause:
The keystore file being imported was either empty or of invalid format.

Action:
Ensure that the keystore being imported is of valid format.

JPS-06557
Mismatch between the values of CSF maps and keys

Category:
Configuration

Cause:
There should be equal number of entries for CSF maps and CSF keys

Action:
Ensure that CSF maps and keys are either both null, or are equal in number.

JPS-06558
Mismatch between the values of key alias/password and CSF map/key

Category:
Configuration

Cause:
There should be equal number of entries for key alias/password and CSF map/key

Action:
Ensure that key alias/password and CSF map/key are equal in number.

JPS-06559
Keystore type {0} not supported

Category:
Configuration

Cause:
The keystore type was not supported.

Action:
Check the list of supported keystore types and specify one of them.

JPS-06560
Failed to import the keystore {0} in stripe {1}. Reason {2}

Category:
Compliance

Cause:

Action:

JPS-06561
Failed to export the keystore {0} in stripe {1}. Reason {2}.

Category:
Compliance

Cause:

Action:

JPS-06562
Failed to load the keystore.

Category:
Compliance

Cause:

Action:

JPS-06563
Failed to save the keystore.

Category:
Compliance

Cause:

Action:

JPS-06564
Method not implemented

Category:
Compliance

Cause:

Action:

JPS-06565
Invalid keystore protection parameter

Category:
Configuration

Cause:
The specified keystore protection type was not supported.

Action:
Ensure that the keystore protection type is a password.

JPS-06566
No trusted certificate found with this alias

Category:
Configuration

Cause:
The specified alias did not refer to a trusted certificate.

Action:
Ensure that the alias refers to a trusted certificate in the keystore.

JPS-06567
Unsupported key type

Category:
Configuration

Cause:
The key type was not supported.

Action:
Ensure that key is either private key or secret key.

JPS-06568
Insufficient permissions for this operation. Reason {0}

Category:
Compliance

Cause:

Action:

JPS-06569
Keystore {0} in app stripe {1} does not exist

Category:
Compliance

Cause:

Action:

JPS-06570
Failed to set keystore policy

Category:
Compliance

Cause:

Action:

JPS-06571
Failed to delete keystore policy

Category:
Compliance

Cause:

Action:

JPS-06572
Null policy name/value not allowed

Category:
Compliance

Cause:

Action:

JPS-06573
Failed to list keystore policies

Category:
Compliance

Cause:

Action:

JPS-06574
Invalid key parameters

Category:
Compliance

Cause:

Action:

JPS-06575
Certificate import failed as the public key in the certificate did not match the one in the keystore.

Category:
Configuration

Cause:
The public key in the certificate does not match the one in the keystore.

Action:
Ensure that the certificate is imported into the alias used for generating certificate request.

JPS-06576
Failed to read {0} with alias {1}.

Category:
Configuration

Cause:
Failed to read {0} with alias {1}.

Action:
Contact the administrator.

JPS-06577
Failed to create private key {0}.

Category:
Configuration

Cause:
Failed to create private key {0}.

Action:
Contact the administrator.

JPS-06578
Cert with alias {0} was invalid.

Category:
Configuration

Cause:
Cert with alias {0} was invalid.

Action:
Contact the administrator.

JPS-06579
Failed to read keystore data.

Category:
Configuration

Cause:
Failed to read keystore data.

Action:
Contact the administrator.

JPS-06580
Failed to check keystore integrity.

Category:
Configuration

Cause:
Failed to check keystore integrity.

Action:
Contact the administrator.

JPS-06581
Failed to load certificates from the keystore.

Category:
Configuration

Cause:
Failed to load certificates from the keystore.

Action:
Contact the administrator.

JPS-06582
Failed to get trusted certs.

Category:
Configuration

Cause:
Failed to get trusted certs

Action:
Contact the administrator.

JPS-06583
Failed to check if audit is enabled.

Category:
Configuration

Cause:
Keystore audit events logging was not enabled.

Action:
Check the audit configuration to ensure auditing enabled.

JPS-06584
Failed to log audit record.

Category:
Configuration

Cause:
Keystore audit event logging failed.

Action:
Contact the administrator.

JPS-06585
Created keystore {0} in stripe {1}

Category:
Compliance

Cause:

Action:

JPS-06586
Deleted keystore {0} in stripe {1}

Category:
Compliance

Cause:

Action:

JPS-06587
Successfully listed keystores in stripe {0}

Category:
Compliance

Cause:

Action:

JPS-06588
Failed to list keystores in stripe {0}

Category:
Compliance

Cause:

Action:

JPS-06589
Successfully got the handle to keystore {0} in stripe {1}

Category:
Compliance

Cause:

Action:

JPS-06590
Failed to get the handle to keystore {0} in stripe {1}

Category:
Compliance

Cause:

Action:

JPS-06591
Successfully changed the password of keystore {0} in stripe {1}

Category:
Compliance

Cause:

Action:

JPS-06592
Successfully generated key pair with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06593
Successfully generated secret key with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06594
Successfully changed password for key with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06595
Successfully listed aliases for keystore {0} in stripe {1}

Category:
Compliance

Cause:

Action:

JPS-06596
Successfully listed properties for secret key with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06597
Failed to list properties for secret key with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06598
Successfully got certificate(s) with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06599
Successfully exported certificate request for key with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06600
Failed to export certificate(s) with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06601
Successfully exported certificate(s) with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06602
Successfully imported the key store entry with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06603
Successfully deleted the key store entry with alias {0} for keystore {1} in stripe {2}

Category:
Compliance

Cause:

Action:

JPS-06604
Successfully imported the keystore {0} in stripe {1}.

Category:
Compliance

Cause:

Action:

JPS-06605
Successfully exported the keystore {0} in stripe {1}.

Category:
Compliance

Cause:

Action:

JPS-06606
Could not create keystore service instance. Reason {0}

Category:
Compliance

Cause:
Could not create keystore service instance

Action:
Contact system administrator

JPS-06607
The keystore service DN {0} is missing in the store; the target DN must be pre-configured.

Category:
Requests/Responses

Cause:
The expected keystore DN {0} was missing.

Action:
Configure this DN during the bootstrap process.

JPS-06608
The farm DN property {0} is invalid or not defined.

Category:
Requests/Responses

Cause:
The farm name property {0} was invalid or not defined.

Action:
Check the configuration of this property.

JPS-06609
The keystore is not initialized.

Category:
Configuration

Cause:
The keystore was not loaded.

Action:
Load the keystore before trying this operation.

JPS-06610
Keystore {0} did not exist.

Category:
Compliance

Cause:

Action:

JPS-06611
The keystore service instance {0} was not initialized.

Category:
Configuration

Cause:
Keystore service was not completely initialized.

Action:
Wait until data source is available and try again later.

JPS-06612
The properties for keystore {0} in stripe {1} were read successfully

Category:
Compliance

Cause:

Action:

JPS-06613
Supported key sizes could not be determined for this algorithm.

Category:
Compliance

Cause:

Action:

JPS-06614
Operation not supported - unable to delete key store {0} in stripe {1}.

Category:
Configuration

Cause:
Deletion of domain trust store or the demo CA key store was not permitted.

Action:
Choose a different key store.

JPS-06615
Operation not supported - unable to delete alias {0} in key store {1} in stripe {2}.

Category:
Configuration

Cause:
Deletion of demo CA key was not permitted.

Action:
Choose a different key alias.

JPS-06616
Missing certificate chain.

Category:
Configuration

Cause:
Certificate chain was null.

Action:
Specify a valid certificate chain.

JPS-06617
Successfully retrieved the attribute {0} from the keystore {1} in stripe {2}.

Category:
Compliance

Cause:

Action:

JPS-06618
Failed to retrieve attribute {0} from the keystore {1} in stripe {2}.

Category:
Compliance

Cause:

Action:

JPS-06619
Key store file keystores.xml integrity check failed. Location: {0}

Category:
Configuration

Cause:
File keystore.xml has been manually edited.

Action:
Restore the keystore file to the last working backup and try again.

JPS-06620
Key store file integrity checker initialization failed. Reason {0}

Category:
Configuration

Cause:
Problem using the bootstrap credential store service.

Action:
Check the bootstrap credential store configuration.

JPS-06621
Cannot change password of a permission protected key store

Category:
Compliance

Cause:

Action:

JPS-06622
Cannot change key password of a permission protected key store

Category:
Compliance

Cause:

Action:

JPS-06623
Invalid KSS URI: {0}

Category:
Compliance

Cause:

Action:

JPS-06624
Cannot synchronize centralized key store(s) from stripe {0} to bootstrap key store(s). Reason {1}

Category:
Configuration

Cause:

Action:

JPS-06625
Invalid component type {0}

Category:
Configuration

Cause:

Action:

JPS-06626
Could not get bootstrap key store service. Reason {0}

Category:
Compliance

Cause:
Could not get bootstrap key store service.

Action:
Verify key store service is correctly configured and initialized.

JPS-06627
Invalid keystore provider type. Value {0}

Category:
Configuration

Cause:
Value of keystore.provider.type is invalid.

Action:
Assign a valid value to keystore.provider.type.

JPS-06628
Key alias {0} corresponds to neither a key nor a trusted certificate in the imported keystore.

Category:
Configuration

Cause:
Given key alias corresponds to neither a key nor a trusted certificate.

Action:
Given key alias should correspond to either a key or a trusted certificate.

JPS-06629
No alias specified so skipping import/export

Category:
Configuration

Cause:
Key aliases should not be null or empty string.

Action:
Ensure that key aliases are neither null nor empty string.

JPS-06630
Import of entry with alias: {0} into appStripe:{1} keystore:{2} skipped as it already exists in the keystore.

Category:
Configuration

Cause:
Alias already exists in the keystore. Alias overwriting while importing not supported.

Action:
Alias to be imported shouldn't pre-exist in the key store.

JPS-06631
Certificate import failed as the minimum number of certificates expected is {0}

Category:
Configuration

Cause:
K required were not given.

Action:
Ensure that minimum number of certificates are imported.

JPS-06632
Invalid key store attribute {0}

Category:
Compliance

Cause:

Action:

JPS-06633
Cannot synchronize component key store(s) under stripe {0} into corresponding wallets. Reason {1}

Category:
Configuration

Cause:

Action:

JPS-06634
One or more of keystores inside application stripe {0} are not permission protected.

Category:
Compliance

Cause:
One or more of keystores inside the application stripe are not permission protected.

Action:
Ensure that all keystores in the application stripe are permission protected.

JPS-06635
Either or both of stripe name {0} and keystore format {1} is null or empty string.

Category:
Compliance

Cause:
Either or both of stripe name and keystore format is null or empty string.

Action:
Ensure that stripe name and keystore format are both non-empty string.

JPS-06636
Application stripe {0} does not exist in keystore.

Category:
Compliance

Cause:
Given application stripe doesn't exist in keystore.

Action:
Provide name of an application stripe that is already existing in keystore.

JPS-06637
Trusted certificate with Subject DN {0} is missing from trust store of keystore.

Category:
Compliance

Cause:
A trusted certificate is missing from trust store of keystore.

Action:
Ensure that the trusted certificate is present in trust store of keystore.

JPS-06638
KeyStore Entry required were not given.

Category:
Configuration

Cause:
KeyStore Entry required were not given.

Action:
Provide KeyStore Entry as input.

JPS-06639
The following aliases were encountered in the keystore: {0}

Category:
Compliance

Cause:

Action:

JPS-06640
Empty alias specified for importing wallet keystore, so skipping import

Category:
Configuration

Cause:
Key aliases of wallet keystore to import should not be empty string.

Action:
Ensure that key aliases of wallet keystore to import are not empty string.

JPS-06641
Invalid keySize format : {0}

Category:
Compliance

Cause:
Cannot set key entry for non-existent stripe and keystore

Action:
This operation is not supported

JPS-06642
Can not determine the JAVA/JRE home,so could not find the cacerts file.

Category:
Compliance

Cause:
Neither environnment variable JAVA_HOME nor system property java.home is specified.

Action:
Ensure that either environnment variable JAVA_HOME or system property java.home is specified.

JPS-06643
JDK cacerts file {0} in use.

Category:
Compliance

Cause:

Action:

JPS-06644
Failed to import JDK cacerts to system/publiccacerts.

Category:
Compliance

Cause:
Importing JDK CA cert failed.

Action:
check log for more details.

JPS-06645
JDK cacerts {0} does not exist.

Category:
Compliance

Cause:
JDK cacerts file {0} does not exist.

Action:
Check the location of JDK cacerts files.

JPS-06646
Private or Secret key found in Trust Store

Category:
Compliance

Cause:

Action:

JPS-06647
Aggregation of two trust stores failed

Category:
Compliance

Cause:
There is a private or secret key entry in the truststore

Action:
Remove the private or secret key entries from the truststore

JPS-06655
The keysize for algorithm {0} can not be less than {1}, but {2} is being used .

Category:
Compliance

Cause:
Keysize is not allowed for specific algorithm

Action:
Use a higher key size for this algorithm.

JPS-06656
Using algorithm {0} is not permitted.

Category:
Compliance

Cause:
The algorithm is not allowed.

Action:
Use a stronger algorithm.

JPS-06657
The format of Subject Alternative Name certificate extension is invalid: {0}.

Category:
Requests/Responses

Cause:
The format of Subject Alternative Name certificate extension is invalid.

Action:
Correct the format of Subject Alternative Name certificate extension.

JPS-06658
Invalid secret key value.

Category:
Configuration

Cause:
Invalid secet key.

Action:
Check the value of secret key.

JPS-06659
Invalid private key value.

Category:
Configuration

Cause:
Invalid private key.

Action:
Check the value of private key.

JPS-06660
Invalid certificate value.

Category:
Configuration

Cause:
Invalid certificate.

Action:
Check the value of certificate.

JPS-06661
Invalid private key or certificate.

Category:
Configuration

Cause:
Invalid private key or certificate.

Action:
Check the value of private key and certificate.

JPS-06662
Import secret key success.

Category:
Compliance

Cause:

Action:

JPS-06663
Import private key and certificate success.

Category:
Compliance

Cause:

Action:

JPS-06664
Import secret key failure.

Category:
Compliance

Cause:

Action:

JPS-06665
Import private key and certificate failure.

Category:
Compliance

Cause:

Action:

JPS-06666
Invalid key password value.

Category:
Configuration

Cause:
Invalid key password.

Action:
Check the value of key password.

JPS-07000
Provide a valid jps configuration file.

Category:
Security

Cause:
The jps configuration file was invalid.

Action:
Refer to the log files for details and correct the error.

JPS-07001
Provide a valid application name.

Category:
Security

Cause:
Application ID was invalid.

Action:
Refer to the log files for details and correct the error.

JPS-07002
Provide a valid jazn-data file. .

Category:
Security

Cause:
The jazn-data file was invalid.

Action:
Refer to the log files for details and correct the error.

JPS-07003
Provide a valid folder name.

Category:
Security

Cause:
The patch delta folder was invalid.

Action:
Provide a valid folder for generating patch delta files.

JPS-07004
ApplicationPolicy object is null/empty.

Category:
Security

Cause:
ApplicationPolicy object was null

Action:
Make sure to create a not null ApplicationPolicy object

JPS-07005
The "{0} " jazn data file does not exists.

Category:
Security

Cause:
Jazn data file does not exists.

Action:
Make sure to provide an existing jazn-data file.

JPS-07006
"{0}" Not a folder. Please provide a valid folder.

Category:
Security

Cause:
Not a folder.

Action:
Make sure to provide a valid folder.

JPS-07007
"{0}" folder does not exists

Category:
Security

Cause:
The folder does not exists.

Action:
Make sure to provide an existing folder.

JPS-07008
The {0} jps configuration file does not exist.

Category:
Security

Cause:
The jps configuration file does not exists.

Action:
Make sure to provide an existing jps configuration file.

JPS-07009
The "{0}" folder for generating patch delta files does not exist.

Category:
Security

Cause:
The folder to generate the patch delta files does not exists.

Action:
Make sure to provide an existing folder.

JPS-07010
The AppRole "{0}" cannot be created. Cause {1} .

Category:
Security

Cause:
The approle could not be created.

Action:
Refer to the log files for details and correct the error.

JPS-07011
The AppRole object is null while persisting to Addition Safe Changes.

Category:
Security

Cause:
The required parameter was null.

Action:
Ensure to provide a valid AppRole Object.

JPS-07012
The ResourceType object is null while persisting to Addition Safe Changes.

Category:
Security

Cause:
The required parameter was null.

Action:
Enusre to provide a valid ResourceType Object.

JPS-07013
The AppRole list is null/empty while persisting to Addition Safe Changes.

Category:
Security

Cause:
The required parameter was null.

Action:
Ensure to provide a valid AppRole List.

JPS-07014
The Resource object is null while persisting to Addition Safe Changes.

Category:
Security

Cause:
The required parameter was null.

Action:
Ensure to pass a valid Resource object.

JPS-07015
The PermissionSet object is null while persisting to Addition Safe Changes.

Category:
Security

Cause:
The required parameter was null.

Action:
Ensure to provide a valid PermissionSet object.

JPS-07016
The Association object is null while persisting to Addition Safe Changes.

Category:
Security

Cause:
The required parameter was null.

Action:
Ensure to provide a valid Association object.

JPS-07017
Internal Error.

Category:
Security

Cause:
That was an internal error.

Action:
Refer to the log files for details and correct the error.

JPS-07018
Application Role: "{0}" cannot be added. Reason {1} .

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07019
Permission Set: "{0}" cannot be added. Reason {1}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07020
Resource: "{0}" cannot be added. Reason {1}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07021
Resource Type "{0}" cannot be added. Reason {1}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07022
Member: name "{0}" ,class "{1}" cannot be granted an application role: "{2}". Reason {3}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07023
Resource Actions: name "{0}", actions "{1}" cannot be added in permission set: "{2}". Reason {3}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07024
Permission: "{0}" cannot be granted to grantee "{1}". Reason {2}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07025
Permission set: "{0}" cannot be granted to grantee "{1}". Reason {2}

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07026
Application Role: "{0}" cannot be modified. Reason {1}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07027
Permission Set: "{0}" cannot be modified. Reason {1}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07028
Resource: "{0}" cannot be modified. Reason {1}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07029
Resource Type: "{0}" cannot be modified. Reason {1}

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07030
Application Role: "{0}" cannot be deleted. Reason {1}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07031
Permission Set: "{0}" cannot be deleted. Reason {1}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07032
Resource: "{0}" cannot be deleted. Reason {1}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07033
Resource Type: "{0}" cannot be deleted. Reason {1}

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07034
Member: name "{0}", class "{1}" cannot be revoked from application role: "{2}". reason {3}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07035
Resource Actions: name "{0}", actions "{1}" cannot be deleted from permission set: "{2}". Reason {3}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07036
Permission: "{0}" cannot be revoked from grantee: "{1}". Reason {2}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07037
Permission set: "{0}" cannot be revoked from grantee: "{1}". Reason {2}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07038
Additions cannot be read. Reason {0}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07039
Deletions cannot be read. Reason {0}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07040
Modifications cannot be read. Reason {0}.

Category:
Security

Cause:
Policy store reported an error.

Action:
Check the Reason and fix the problem.

JPS-07041
The argument "{0}" is not applicable for phase "{1}".

Category:
Security

Cause:
Extra argument provided

Action:
Please provide only relavent parameters

JPS-07042
Illegal value provided for argument "{0}".

Category:
Security

Cause:
Illegal value provided for an argument

Action:
Please provide a legal value for the argument.

JPS-07043
Cannot find application policy {0}.

Category:
Security

Cause:
Could not find application policy {0}.

Action:
Check the application name passed.

JPS-07044
Cannot retrieve newline application policy.

Category:
Security

Cause:
Could not retrieve newline application policy.

Action:
Check the application name passed.

JPS-07045
Cannot retrieve baseline application policy.

Category:
Security

Cause:
Could not retrieve baseline application policy.

Action:
Check the application name passed.

JPS-07046
Cannot retrieve customer application policy.

Category:
Security

Cause:
Could not retrieve customer application policy.

Action:
Check the application name passed.

JPS-07047
This artifact is newly added in patch version.

Category:
Security

Cause:
Policy store doesn't suport metadata

Action:
Update policy store

JPS-07055
Policy entry is null.

Category:
Security

Cause:
{0} Policy entry is null.

Action:
No actions are required.

JPS-07056
Addition conflicts initialization failed.

Category:
Security

Cause:
Internal Error occured when attempting to load Addition Conflicts from Patch Delta.

Action:
Check the logs.

JPS-07057
Modification conflicts initialization failed.

Category:
Security

Cause:
Internal Error occured when attempting to load Modification Conflicts from Patch Delta.

Action:
Check the logs.

JPS-07058
Deletion conflicts initialization failed.

Category:
Security

Cause:
Internal Error occured when attempting to load Deletion Conflicts from Patch Delta.

Action:
Check the logs.

JPS-07059
Conflicting addition changes in the patch have been identified. Silent Apply process halted. Resolve the conflicts and Apply the patch.

Category:
Security

Cause:
Addition conflicts are not resolved.

Action:
Resolve addition conflicts.

JPS-07060
Conflicting modification changes in the patch have been identified. Silent Apply process halted. Resolve the conflicts and Apply the patch.

Category:
Security

Cause:
Modification conflicts are not resolved.

Action:
Resolve modification conflicts.

JPS-07061
Conflicting deletion changes in the patch have been identified. Silent Apply process halted. Resolve the conflicts and Apply the patch.

Category:
Security

Cause:
Deletion conflicts are not resolved.

Action:
Resolve deletion conflicts.

JPS-07062
Additions Writer initialization failed for resolve.

Category:
Security

Cause:
Additions Writer initialization failed for resolve.

Action:
Check the logs.

JPS-07063
Deletions Writer initialization failed for resolve.

Category:
Security

Cause:
Additions Writer initialization failed for resolve.

Action:
Check the logs.

JPS-07064
Modifications Writer initialization failed for resolve.

Category:
Security

Cause:
Modification Writer initialization failed for resolve.

Action:
Check the logs.

JPS-07065
Dependency artifact {0} is not resolved for artifact {1}.

Category:
Security

Cause:
Dependency artifact {0} is not resolved for artifact {1}.

Action:
Check the resolutions.

JPS-07066
Dependency artifact {0} resolution is not valid for artifact {1}.

Category:
Security

Cause:
Dependency artifact {0} resolution is not valid for artifact {1}.

Action:
Check the resolutions.

JPS-07067
Artifact not resolved {0}.

Category:
Security

Cause:
Artifact not resolved {0}.

Action:
Check the resolutions.

JPS-07069
Deletion of member {0} of permission set {1} renders the permission set empty.

Category:
Security

Cause:
Deletion of member will render Permission set empty

Action:
Check the resolutions.

JPS-07070
The argument {0} is not passed

Category:
Security

Cause:
The required argument is not passed.

Action:
Provide the required argument.

JPS-07071
Deletion Changes in the patch have been identified. Applying the changes will permanently delete policy store artifacts. Silent Apply process halted. Review the changes and Apply the patch.

Category:
Security

Cause:
Addition Safe changes and Modification Safe changes have been applied.However, Deletion conflicts are not resolved.

Action:
Resolve deletion conflicts.

JPS-07077
Cannot generate report. Reason {0}

Category:
Security

Cause:
Report generation failed.

Action:
Check the logs.

JPS-07078
Report file {0} path is invalid.

Category:
Security

Cause:
Report file specified is not a valid file path.

Action:
Specify a valid file path.

JPS-07079
Report file {0} cannot be created in the given directory.

Category:
Security

Cause:
The directory doesn't have write permission.

Action:
Specify a directory which has write permission.

JPS-07080
Report file {0} already exists.

Category:
Security

Cause:
Report file exists.

Action:
Specify a non existing file.

JPS-07081
Could not find policystore in "{0}" jps context in production config.

Category:
Security

Cause:
Could not find policystore in {0} jps context in production config.

Action:
Provide a service instance for policystore in the {0} jps context in production config.

JPS-07082
Loading base policy store complete in {0}.

Category:
Security

Cause:
Loading base policy store complete in {0}.

Action:
No actions are required.

JPS-07083
Initializing Application Policy Comparator complete in {0}.

Category:
Security

Cause:
Initializing Application Policy Comparator complete in {0}.

Action:
No actions are required.

JPS-07084
Loading new policy store complete in {0}.

Category:
Security

Cause:
Loading new policy store complete in {0}.

Action:
No actions are required.

JPS-07085
Oracle Delta calculation complete in {0}.

Category:
Security

Cause:
Oracle Delta calculation complete in {0}.

Action:
No actions are required.

JPS-07086
Production application policy store object created in {0}.

Category:
Security

Cause:
Production application policy store object created in {0}.

Action:
No actions are required.

JPS-07087
Customer delta created in {0}.

Category:
Security

Cause:
Customer delta created in {0}.

Action:
No actions are required.

JPS-07088
Patch delta created in {0}.

Category:
Security

Cause:
Patch delta created in {0}.

Action:
No actions are required.

JPS-07089
Report File created in {0}.

Category:
Security

Cause:
Report file created in {0}.

Action:
No actions are required.

JPS-07090
Customer delta files created in {0}.

Category:
Security

Cause:
Customer delta files created in {0}.

Action:
No actions are required.

JPS-07093
The Role category object is null while persisting to Addition Safe Changes.

Category:
Security

Cause:
The required parameter was null.

Action:
Enusre to provide a valid RoleCategory Object.

JPS-07101
Beginning to apply additions...

Category:
Security

Cause:
Beginning to apply additions...

Action:
No actions are required.

JPS-07102
Additions applied in {0}

Category:
Security

Cause:
Additions applied in {0}.

Action:
No actions are required.

JPS-07103
Beginning to apply modifications...

Category:
Security

Cause:
Beginning to apply modifications...

Action:
No actions are required.

JPS-07104
Modifications applied in {0}

Category:
Security

Cause:
Modifications applied in {0}.

Action:
No actions are required.

JPS-07105
Beginning to apply deletions...

Category:
Security

Cause:
Beginning to apply deletions...

Action:
No actions are required.

JPS-07106
Deletions applied in {0}

Category:
Security

Cause:
Deletions applied in {0}.

Action:
No actions are required.

JPS-07107
{0} Application roles added.

Category:
Security

Cause:
{0} Application roles added.

Action:
No actions are required.

JPS-07108
{0} Role categories added.

Category:
Security

Cause:
{0} Role categories added.

Action:
No actions are required.

JPS-07109
{0} Resource type entries added.

Category:
Security

Cause:
{0} Resource type entries added.

Action:
No actions are required.

JPS-07110
{0} Resource entries added.

Category:
Security

Cause:
{0} Resource entries added.

Action:
No actions are required.

JPS-07111
{0} Permission set entries added.

Category:
Security

Cause:
{0} Permission set entries added.

Action:
No actions are required.

JPS-07112
{0} Application role membership entries added.

Category:
Security

Cause:
{0} Application role membership entries added.

Action:
No actions are required.

JPS-07113
{0} Application role categories entries added.

Category:
Security

Cause:
{0} Application role categories entries added.

Action:
No actions are required.

JPS-07114
{0} Resources to permission sets added.

Category:
Security

Cause:
{0} Resources to permission set entries added.

Action:
No actions are required.

JPS-07115
{0} Permission set membership entries added.

Category:
Security

Cause:
{0} Permission set membership entries added.

Action:
No actions are required.

JPS-07116
{0} Grantee to permission set entries added.

Category:
Security

Cause:
{0} Grantee to permission set entries added.

Action:
No actions are required.

JPS-07117
{0} Grantee to permission membership entries added.

Category:
Security

Cause:
{0} Grantee to permission membership entries added.

Action:
No actions are required.

JPS-07118
{0} Application roles modified.

Category:
Security

Cause:
{0} Application roles modified.

Action:
No actions are required.

JPS-07119
{0} Role categories modified.

Category:
Security

Cause:
{0} Role categories modified.

Action:
No actions are required.

JPS-07120
{0} Resource type entries modified.

Category:
Security

Cause:
{0} Resource type entries modified.

Action:
No actions are required.

JPS-07121
{0} Resource entries modified.

Category:
Security

Cause:
{0} Resource entries modified.

Action:
No actions are required.

JPS-07122
{0} Permission set entries modified.

Category:
Security

Cause:
{0} Permission set entries modified.

Action:
No actions are required.

JPS-07123
{0} Resources to permission sets added.

Category:
Security

Cause:
{0} Resources to permission set entries modified.

Action:
No actions are required.

JPS-07124
{0} Grantee to permission membership entries modified.

Category:
Security

Cause:
{0} Grantee to permission membership entries modified.

Action:
No actions are required.

JPS-07125
Dissociated {0} members from application roles.

Category:
Security

Cause:
Deassociated {0} members and application roles.

Action:
No actions are required.

JPS-07126
Dissociated {0} categories from application roles.

Category:
Security

Cause:
Deassociated {0} categories and application roles.

Action:
No actions are required.

JPS-07127
Dissociated {0} resources from permission sets.

Category:
Security

Cause:
Deassociated {0} resources and permission sets.

Action:
No actions are required.

JPS-07128
Revoked {0} permission sets from grantees.

Category:
Security

Cause:
Revoked {0} permission sets from grantees.

Action:
No actions are required.

JPS-07129
Revoked {0} permissions from grantees.

Category:
Security

Cause:
Revoked {0} permissions from grantees.

Action:
No actions are required.

JPS-07130
{0} Application roles deleted.

Category:
Security

Cause:
{0} Application roles deleted.

Action:
No actions are required.

JPS-07131
{0} Role categories deleted.

Category:
Security

Cause:
{0} Role categories deleted.

Action:
No actions are required.

JPS-07132
{0} Permission set entries deleted.

Category:
Security

Cause:
{0} Permission set entries deleted.

Action:
No actions are required.

JPS-07133
{0} Resource entries deleted.

Category:
Security

Cause:
{0} Resource entries deleted.

Action:
No actions are required.

JPS-07134
{0} Resource type entries deleted.

Category:
Security

Cause:
{0} Resource type entries deleted.

Action:
No actions are required.

JPS-07135
Progress - Apply Additions ---------- {0}% Done

Category:
Security

Cause:
Progress...Apply additions

Action:
No actions are required.

JPS-07136
Progress - Apply Modifications ---------- {0}% Done

Category:
Security

Cause:
Progress...Apply modifications

Action:
No actions are required.

JPS-07137
Progress - Apply Deletions ---------- {0}% Done

Category:
Security

Cause:
Progress...Apply deletions

Action:
No actions are required.

JPS-07138
Dissociated of members from application roles (skipped, not applicable).

Category:
Security

Cause:
Dissociation of members from application roles (skipped, not applicable)

Action:
No actions are required.

JPS-07139
Dissociation of categories from application roles (skipped, not applicable)

Category:
Security

Cause:
Disassociation of categories from application roles (skipped, not applicable)

Action:
No actions are required.

JPS-07140
Dissociation of resources from permission sets (skipped, not applicable).

Category:
Security

Cause:
Disassociation of resources from permission sets (skipped, not applicable)

Action:
No actions are required.

JPS-07141
Revoke of permission sets from grantees (skipped, not applicable).

Category:
Security

Cause:
Revoke of permission sets from grantees (skipped, not applicable)

Action:
No actions are required.

JPS-07142
Revoke of permissions from grantees (skipped, not applicable).

Category:
Security

Cause:
Revoke of permissions from grantees (skipped, not applicable)

Action:
No actions are required.

JPS-07143
Application roles deletion (skipped, not applicable).

Category:
Security

Cause:
Deletion of application roles (skipped, not applicable)

Action:
No actions are required.

JPS-07144
Role categories deletion (skipped, not applicable).

Category:
Security

Cause:
Deletion of role categories (skipped, not applicable)

Action:
No actions are required.

JPS-07145
Permission set entries deletion (skipped, not applicable).

Category:
Security

Cause:
Deletion of permission sets (skipped, not applicable)

Action:
No actions are required.

JPS-07146
Resource entries deletion (skipped, not applicable)

Category:
Security

Cause:
Deletion of resources (skipped, not applicable)

Action:
No actions are required.

JPS-07147
Resource type entries deletion (skipped, not applicable).

Category:
Security

Cause:
Deletion of resource types (skipped, not applicable)

Action:
No actions are required.

JPS-07148
Deletions not applicable when the silent flag is on.

Category:
Security

Cause:
Deletions not applicable when the silent flag is enabled

Action:
No actions are required.

JPS-07150
You can set only one of the two flags - {0} or {1} but not both.

Category:
Security

Cause:
Dual flags have been set. This is not permitted

Action:
Set only one of the two flags - {0} or {1}

JPS-07151
role member {0} of application role: {1} not found.

Category:
Security

Cause:
role member {0} of application role: {1} not found

Action:
Add back role member: {0} or run patching analysis again

JPS-07152
Name collisions have been identified. The patch process halted. Eliminate the collisions by renaming or removing artifacts in production store. Please find artifacts which have name collision between production store and patch version in file {0}.

Category:
Security

Cause:
Name collisions exist.

Action:
Eliminate the name collisions by renaming or removing the policy artifacts in production store.

JPS-07156
{0} Policy rule entries were added.

Category:
Security

Cause:
{0} Policy rule entries added.

Action:
No actions are required.

JPS-07157
{0} Policy entries were added.

Category:
Security

Cause:
{0} Policy entries added.

Action:
No actions are required.

JPS-07158
{0} Policy to permission set entries added.

Category:
Security

Cause:
{0} Policy to permission set entries added.

Action:
No actions are required.

JPS-07159
{0} Policy to policy rule entries were added.

Category:
Security

Cause:
{0} Policy to policy rule entries added.

Action:
No actions are required.

JPS-07160
{0} Policy to grantee entries added.

Category:
Security

Cause:
{0} Policy to grantee entries added.

Action:
No actions are required.

JPS-07161
{0} Policies entries were modified.

Category:
Security

Cause:
{0} Policies entries modified.

Action:
No actions are required.

JPS-07162
{0} Policy rules entries were modified.

Category:
Security

Cause:
{0} Policy rules entries modified.

Action:
No actions are required.

JPS-07163
{0} Policy rules were deleted from policies.

Category:
Security

Cause:
Deleted {0} policy rules from policies.

Action:
No actions are required.

JPS-07164
{0} Principals were deleted from policy.

Category:
Security

Cause:
Deleted {0} principals from policy.

Action:
No actions are required.

JPS-07165
{0} Permission Sets were deleted from policy.

Category:
Security

Cause:
Deleted {0} Permission Set from policy.

Action:
No actions are required.

JPS-07166
{0} Policy entries were deleted.

Category:
Security

Cause:
{0} Policy entries deleted.

Action:
No actions are required.

JPS-07167
{0} Policy rule entries were deleted.

Category:
Security

Cause:
{0} Policy rule entries deleted.

Action:
No actions are required.

JPS-07168
Policy rule entry is null.

Category:
Security

Cause:
{0} Policy rule entry is null.

Action:
No actions are required.

JPS-07169
Delta between patch jazn-data and production policystore was written to report in {0}.

Category:
Security

Cause:
Delta between patch jazn-data and production policystore was written to report in {0}.

Action:
No actions are required.

JPS-07170
Delta between patch jazn-data and production policystore was calculated in {0}.

Category:
Security

Cause:
Delta between patch jazn-data and production policystore was calculated in {0}.

Action:
No actions are required.

JPS-07171
Privilege changes of user or group report between baseline jazn-data and production policystore was created in {0}.

Category:
Security

Cause:
User or group's privilege changes report between baseline jazn-data and production policystore was created in {0}.

Action:
No actions are required.

JPS-07172
Delta between production and baseline jazn-data was validated in {0}.

Category:
Security

Cause:
Policy customization between production and baseline jazn-data was validated in {0}.

Action:
No actions are required.

JPS-07173
Enterprise role privilege changes between production and baseline jazn-data was validated in {0}.

Category:
Security

Cause:
Enterprise user or role privilege changes between production and baseline jazn-data was validated in {0}.

Action:
No actions are required.

JPS-07174
Enterprise user or role privilege validation failed for record: {0}.

Category:
Security

Cause:
Enterprise user or role privilege validation failed for record

Action:
Check the usergroup-privilege-validate-result file for more details

JPS-07175
Policy change validation failed for record: {0}.

Category:
Security

Cause:
Policy change validation failed for record

Action:
Check the policy-validate-result file for more details

JPS-07176
Patch jazn data file {0} will be ignored since this is forceTag mod.

Category:
Security

Cause:
Patch jazn data file {0} will be ignored since this is forceTag mod.

Action:
No action

JPS-07177
Patch application policy name {0} will be ignored since this is forceTag mod.

Category:
Security

Cause:
Patch application policy name {0} will be ignored since this is forceTag mod.

Action:
No action

JPS-07178
Patch delta folder {0} will be ignored since this is forceTag mod.

Category:
Security

Cause:
Patch delta folder {0} will be ignored since this is forceTag mod.

Action:
No action

JPS-07179
Tagging {0} {1} completed in {2}.

Category:
Security

Cause:
Tagging {0} {1} completed in {2}.

Action:
No action

JPS-07180
usergroup-privilege report file {0} not found.

Category:
Security

Cause:
usergroup-privilege report file {0} not found

Action:
Please check the phase used in patching policy store, this file is generated in report phase.

JPS-07181
Metadata support is required on application {0} when there is no baseline file.

Category:
Security

Cause:
Metadata support is required on application {0} when there is no baseline file.

Action:
Please make sure the application policy is supporting meta data when there is no baseline file.

JPS-07182
Report phase requires base line file provisioned.

Category:
Security

Cause:
Report phase requires baseline file.

Action:
Please make sure there is baseline file provisioned during report phase

JPS-07500
Trust protocol {0} is not supported.

Category:
Security

Cause:
Requested trust protocol is not supported

Action:
Provide correct trust protocol

JPS-07501
Token context is invalid.

Category:
Security

Cause:
Token context object is empty or does not contain required parameters

Action:
Check token context object contains required parameter

JPS-07502
Trust Service token provider {0} is not found.

Category:
Security

Cause:
Token provider not configured in the jps-config.xml file

Action:
Check jps-config.xml file and verify that requested token provider is correctly configured

JPS-07503
Trust Service token provider class name {0}.

Category:
Security

Cause:
Token provider class loading

Action:
No action required

JPS-07504
Trust Service Keystore initialization failed.

Category:
Security

Cause:
Keystore is is missing or not configured correctly

Action:
Check the keystore and ensure that necessary certificates and keys are present

JPS-07505
Trust service provider protocol {0}

Category:
Security

Cause:
Trust Service provider protocol information

Action:
No action required

JPS-07506
Token context creation failed.

Category:
Security

Cause:
Incorrct protocol or associated provider configuration.

Action:
Check protocol and associated provider configuration

JPS-07507
Token issue operation

Category:
Security

Cause:
Trust service token issue opertion.

Action:
No action required

JPS-07508
Token issue operation failed.

Category:
Security

Cause:
Trust service token issue opertion failed.

Action:
Check provider configuration

JPS-07509
Invalid token operation

Category:
Security

Cause:
Invalid Trust Service token opertion.

Action:
Check invoked operation name

JPS-07510
Token validate operation.

Category:
Security

Cause:
Trust Service validate token opertion.

Action:
No action required

JPS-07511
Validate operation failed.

Category:
Security

Cause:
Trust service token validate opertion failed.

Action:
Check provider configuration

JPS-07512
Missing token issuer identity.

Category:
Security

Cause:
Token issuer identity missing.

Action:
Provide token issuer identity

JPS-07513
Invalid subject confirmation method.

Category:
Security

Cause:
Invalid subject confirmation method.

Action:
Provide correct subject confirmation method

JPS-07514
Token audience restriction condition check failed.

Category:
Security

Cause:
Invalid token audience condition.

Action:
Check the audience condition

JPS-07515
Token signature validation failed.

Category:
Security

Cause:
Invalid token signature.

Action:
Check token integrity and verify signature using correct certificate

JPS-07516
Invalid token.

Category:
Security

Cause:
Invalid token.

Action:
Check token integrity.

JPS-07517
Input token is not an instance of GenericToken class.

Category:
Security

Cause:
Input token is not an instance of GenericToken class.

Action:
Check the token object class

JPS-07518
Input token is not an instance of UsernameToken class

Category:
Security

Cause:
Input token is not an instance of UsernameToken class.

Action:
Check the token object class

JPS-07519
Setting subject conformation method failed.

Category:
Security

Cause:
Invalid token object.

Action:
Check the token object

JPS-07520
Token signing failed.

Category:
Security

Cause:
Token signing key is unavailable.

Action:
Check the keystore and verify that signing key is present

JPS-07521
Token signature is not available.

Category:
Security

Cause:
Unsigned token.

Action:
No action required.

JPS-07522
Token is not valid yet {0}

Category:
Security

Cause:
Token is not valid yet.

Action:
Check the token validity start date.

JPS-07523
Token has expired {0}

Category:
Security

Cause:
Token has expired.

Action:
Check the token validity end date.

JPS-07524
Certificate is unavailable {0}

Category:
Security

Cause:
Certificate is not available.

Action:
Check the keystore and ensure that the certificate is present.

JPS-07525
Private key is unavailable

Category:
Security

Cause:
Private key is not available.

Action:
Check the keystore and ensure that the private key is present.

JPS-07526
Initializing provider

Category:
Security

Cause:
Provider is initiliazing.

Action:
None

JPS-07527
Shutting down provider

Category:
Security

Cause:
Provider is shutting down.

Action:
None

JPS-07528
Received unknown token type {0}

Category:
Security

Cause:
Received token type is unknown.

Action:
Check the provided token.

JPS-07529
Received unknown token class {0}

Category:
Security

Cause:
Token class is unknown.

Action:
Check the token class.

JPS-07530
Invalid token type or token not found

Category:
Security

Cause:
Invalid token authentication type specified.

Action:
Check the token authentication type.

JPS-07531
Input token is not an instance of {0}

Category:
Security

Cause:
Specified insance is not correct.

Action:
Check the instance type validity.

JPS-07532
Instance of {0} is invalid

Category:
Security

Cause:
Specified instance is invalid.

Action:
Check the specified instance and ensure that it is correct

JPS-07533
Received empty token byte array

Category:
Security

Cause:
Given token is empty.

Action:
Check the token content and ensure that it is not empty.

JPS-07534
Trust service configuration is not valid

Category:
Security

Cause:
Invalid configuration parameters.

Action:
Check the configuration parameters.

JPS-07535
Using {0} Trust service configuration

Category:
Security

Cause:
Configuration type used by Trust Service

Action:
None

JPS-07536
Token credential missing

Category:
Security

Cause:
Token signing or validation credential missing.

Action:
Provide correct credential.

JPS-07537
Token signature missing

Category:
Security

Cause:
Token signature missing.

Action:
Check the token for integrity.

JPS-07538
The input token is not specified

Category:
Security

Cause:
Input token not provided.

Action:
Check if the token has been provided.

JPS-07539
Token signing method is not specified

Category:
Security

Cause:
Token signing algorithm parameter missing.

Action:
Check the token signing algorithm parameter.

JPS-07540
Token signing method is invalid

Category:
Security

Cause:
Token signing algorithm parameter invalid

Action:
Check the specified token signing algorithm.

JPS-07541
Token signing private key is not specified

Category:
Security

Cause:
Token signing private key missing.

Action:
Check the token signing private key parameter.

JPS-07542
Token signing certificate is not specified

Category:
Security

Cause:
Token signing certificate missing.

Action:
Check the token signing certificate parameter.

JPS-07543
Token signing credential is not specified

Category:
Security

Cause:
Token signing credential missing.

Action:
Check the token signing credential parameter.

JPS-07544
The specified token type is invalid

Category:
Security

Cause:
The token type is not supported.

Action:
Check the token type parameter.

JPS-07545
Invalid TokenContext class

Category:
Security

Cause:
Internal Error. The correct TokenContext class is not created.

Action:
Provide the correct TokenProvider class in trust configurations.

JPS-07546
Token cannot be issued for virtual or anonymous user

Category:
Security

Cause:
Trust token cannot be issued for anonymous or virtual users

Action:
Ensure usage of Trust service is limited to users present in configured identity store.

JPS-07600
Application policy for stripe name {0} not found. Nothing to undeploy

Category:
Security

Cause:
No associated application policies

Action:
Check application policy setup or contact system administrator

JPS-07601
Complete staging offline deployment for application {0} in {1}

Category:
Security

Cause:
Complete staging offline deployment for application {0} in {1}

Action:
No action required

JPS-07602
Removal of application policy failed. Reason: {0}.

Category:
Security

Cause:
Exception in removing application policy

Action:
Check application policy setup or contact system administrator

JPS-07603
Cannot purge changelog. Reason {0}.

Category:
Security

Cause:
Purge changelog failed.

Action:
Check policystore configuration.

JPS-07604
Wrong policy combining algorithm name {0} is used.

Category:
Security

Cause:
wrong policy combining algorithm name was used

Action:
Check combining algorithm name being used

JPS-07605
Unsupported policy combining algorithm name {0} is used.

Category:
Security

Cause:
Unsupported policy combining algorithm name was used

Action:
Check combining algorithm name being used

JPS-07606
Cannot clean applications. Reason {0}.

Category:
Security

Cause:
Clean applications failed.

Action:
Refer to the log files for details and correct the error.

JPS-07607
{0} is used in source, but it is not supported by destination policy store.

Category:
Security

Cause:
Source contains policy artifacts that is not supported by destination policy store

Action:
Make sure source only contain policy artifacts which are compatible with destination policy store

JPS-07608
ERROR:not allowed to modify seed policy store {0}.

Category:
Security

Cause:
ERROR:not allowed to modify seed policy store {0}.

Action:
Refer to the log files for details and correct the error.

JPS-07609
AttributeName {0} supplied should start with alphabet or an underscore. Name cannot contain characters other than alphanumeric, underscore, colon, dot and hyphen.

Category:
Security

Cause:
AttributeName {0} supplied should start with alphabet or an underscore. Name cannot contain characters contain other than alphanumeric, underscore, colon, dot and hyphen.

Action:
Ensure attribute name is of correct datatype.

JPS-07610
Function Name {0} supplied should start with alphabet or an underscore. Name cannot contain characters other than alphanumeric, underscore, colon, dot and hyphen.

Category:
Security

Cause:
Function Name {0} supplied should start with alphabet or an underscore. Name cannot contain characters contain other than alphanumeric, underscore, colon, dot and hyphen.

Action:
Ensure function name is of correct datatype.

JPS-08000
Subject object {0} is not supported.

Category:
Security

Cause:
Specified Object type is not supported by the provider for Subject.

Action:
Check the document for supported object types.

JPS-08001
Action object {0} is not supported.

Category:
Security

Cause:
Specified Object type is not supported by the provider for Action.

Action:
Check the document for supported object types.

JPS-08002
Resource object {0} is not supported.

Category:
Security

Cause:
Specified Object type is not supported by the provider for Resource.

Action:
Check the document for supported object types.

JPS-08003
Environment object {0} is not supported.

Category:
Security

Cause:
Specified Object type is not supported by the provider for Environment.

Action:
Check the document for supported object types.

JPS-08004
Invalid resource string: {0}.

Category:
Security

Cause:
The resource string is invalid.

Action:
Check the document for the resource string format.

JPS-08005
Subject cannot be null.

Category:
Security

Cause:
The subject is null.

Action:
Use a valid subject.

JPS-08006
Action cannot be null.

Category:
Security

Cause:
The action is null.

Action:
Use a valid action.

JPS-08007
Resource cannot be null.

Category:
Security

Cause:
The resource is null.

Action:
Use a valid resource.

JPS-08008
Action list cannot be null or empty.

Category:
Security

Cause:
The action list is null or empty.

Action:
Use a valid action list.

JPS-08009
Resource list cannot be null or empty.

Category:
Security

Cause:
The resource list is null or empty.

Action:
Use a valid resource list.

JPS-08010
The size of action list and resource list is different.

Category:
Security

Cause:
The size of action list and resource list is different.

Action:
The size of action list should be identical to the size of resource list.

JPS-08011
Subject object {0} is not a valid subject on platform {1}.

Category:
Security

Cause:
The subject object is not a valid subject on current platform.

Action:
Use a valid subject.

JPS-08012
Scope cannot be null or empty.

Category:
Security

Cause:
Scope is null or empty.

Action:
Use a valid scope.

JPS-08013
Query Type cannot be null.

Category:
Security

Cause:
Query Type is null.

Action:
Use a valid Query Type.

JPS-08014
Invalid scope string: {0}.

Category:
Security

Cause:
The scope string is invalid.

Action:
Check the document for the scope string format.

JPS-08015
Invalid search scope string: {0}.

Category:
Security

Cause:
The search scope in scope string is invalid.

Action:
Check the document for the scope string format.

JPS-08016
An error has occurred while processing the PepResponse result.

Category:
Security

Cause:
An error has occurred while processing the PepResponse results.

Action:
Check the policy setup and client code.

JPS-08017
Invalid resource string: {0}. Please provide a fully qualified resource string.

Category:
Security

Cause:
Fully qualified resource string is required.

Action:
Please specify application ID, resource type and resource name.

JPS-08018
The configured policy provider {0} does not implement AzPolicy interface.

Category:
Security

Cause:
The configured policy provider does not implement AzPolicy interface.

Action:
You must configure policy provider that implements AzPolicy interface, e.g. by calling Policy.setPolicy().

JPS-08019
Requested operation is not supported.

Category:
Security

Cause:
Requested operation is not supported.

Action:
Do not invoke unsupported operation.

JPS-08020
The authorization service instance is invalid.

Category:
Security

Cause:
The authorization service instance is invalid.

Action:
Check the service instance and ensure that is a supported authorization service instance.

JPS-08021
The input configuration parameter is invalid.

Category:
Security

Cause:
The input configuration parameter is invalid.

Action:
Check the configuration parameter validity.

JPS-08022
Incorrect authorization service instance type.

Category:
Security

Cause:
Incorrect authorization service instance type.

Action:
Check the authorization service instance type.

JPS-08023
The environment parameter is missing.

Category:
Security

Cause:
The environment paramater is missing.

Action:
Check the environment paramater.

JPS-08024
Policy context parameter is missing.

Category:
Security

Cause:
Policy context parameter is missing.

Action:
Check the policy context paramater.

JPS-08025
Session context parameter is missing.

Category:
Security

Cause:
Session context parameter is missing.

Action:
Check the session paramater.

JPS-08026
Database connection parameter is missing.

Category:
Security

Cause:
Database connection parameter is missing or not a right type.

Action:
Check the database connection paramater.

JPS-08027
Security predicate parameter is missing.

Category:
Security

Cause:
Security predicate parameter is missing.

Action:
Check the security predicate paramater.

JPS-08028
Cannot find appName attribute in resource collection.

Category:
Security

Cause:
Can't find appName attribute in resource collection.

Action:
Add appName attribute to resource collection.

JPS-08029
Privilege parameter is missing or not a right type

Category:
Security

Cause:
Privilege parameter is missing or not a right type.

Action:
Check the privilege paramater.

JPS-08030
DB object parameter is missing or not a right type.

Category:
Security

Cause:
DB object parameter is missing or not a right type.

Action:
Check the DB object paramater.

JPS-08031
Client env parameter is not a right type.

Category:
Security

Cause:
Client env parameter is not a right type.

Action:
Check the client env paramater.

JPS-08032
Client env parameter has unsupported value.

Category:
Security

Cause:
Client env parameter has unsupported value.

Action:
Check the client env paramater.

JPS-08033
Check privilege mode parameter has unsupported value.

Category:
Security

Cause:
Check privilege mode parameter has unsupported value.

Action:
Check the Check privilege paramater.

JPS-08034
Value of parameter {0} should be type {1}, but has a wrong type {2}.

Category:
Security

Cause:
Invalid parameter type

Action:
Check the paramater.

JPS-08035
Type of RAS parameter value is not supported.

Category:
Security

Cause:
Type of RAS parameter value is not supported.

Action:
Do not use unsupported type for RAS parameter value.

JPS-08036
Invalid data type in Subject collection, it only accepts RuntimeAttribute.

Category:
Security

Cause:
Invalid data type in Subject collection, it only accepts RuntimeAttribute.

Action:
Use RuntimeAttribute in Subject collection.

JPS-08037
Invalid data type in Action collection, it only accepts RuntimeAttribute.

Category:
Security

Cause:
Invalid data type in Action collection, it only accepts RuntimeAttribute.

Action:
Use RuntimeAttribute in Action collection.

JPS-08038
Invalid data type in Resource collection, it only accepts RuntimeAttribute.

Category:
Security

Cause:
Invalid data type in Resource collection, it only accepts RuntimeAttribute.

Action:
Use RuntimeAttribute in Resource collection.

JPS-08500
Component audit definition {0} already exists.

Category:
Security

Cause:
Component audit definition {0} already exists.

Action:
Check given component type.

JPS-08501
Failed to create component audit definition {0}. Reason: {1}.

Category:
Security

Cause:
Failed to create component audit definition {0}. Reason: {1}.

Action:
See error message.

JPS-08502
Failed to search database mapping table for component {0}. Reason: {1}.

Category:
Security

Cause:
Failed to search database mapping table for component {0}. Reason: {1}.

Action:
See error message.

JPS-08503
Cannot search audit definition for component {0}. Reason: {1}.

Category:
Security

Cause:
Cannot search audit definition for component {0}. Reason: {1}.

Action:
See error message.

JPS-08504
Failed to search generic attribute groups. Reason: {0}.

Category:
Security

Cause:
Failed to search generic attribute groups. Reason: {0}.

Action:
See error message.

JPS-08505
Failed to create database mapping table for component {0}. Reason: {1}.

Category:
Security

Cause:
Failed to create database mapping table for component {0}. Reason: {1}.

Action:
See error message.

JPS-08506
Failed to create filter config for component {0}. Reason: {1}.

Category:
Security

Cause:
Failed to create filter config for component {0}. Reason: {1}.

Action:
See error message.

JPS-08507
Component audit definition {0} does not exist.

Category:
Security

Cause:
Component audit definition {0} does not exist.

Action:
Check given component type.

JPS-08508
Failed to search filter config for component {0}. Reason: {1}.

Category:
Security

Cause:
Failed to search filter config for component {0}. Reason: {1}.

Action:
See error message.

JPS-08509
Failed to update filter config for component {0}. Reason: {1}.

Category:
Security

Cause:
Failed to update filter config for component {0}. Reason: {1}.

Action:
See error message.

JPS-08510
The expected audit store DN {0} was missing.

Category:
Security

Cause:
The expected audit store DN {0} was missing.

Action:
Configure this DN during the bootstrap process.

JPS-08511
Audit store was not fully initialized until data source is available.

Category:
Security

Cause:
Audit store was not fully initialized until data source is available.

Action:
Wait and retry later.

JPS-08512
Failed to retrieve value. Reason: {0}.

Category:
Security

Cause:
Failed to retrieve value. Reason: {0}.

Action:
See error message.

JPS-08513
Failed to search component types. Reason: {0}.

Category:
Security

Cause:
Failed to search component types. Reason: {0}.

Action:
See error message.

JPS-08514
Failed to search system XLF. Reason: {0}.

Category:
Security

Cause:
Failed to search system XLF. Reason: {0}.

Action:
See error message.

JPS-08515
Failed to search XLF for component {0}. Reason: {1}.

Category:
Security

Cause:
Failed to search XLF for component {0}. Reason: {1}.

Action:
See error message.

JPS-08516
Failed to search system definition. Reason: {0}.

Category:
Security

Cause:
Failed to search system definition. Reason: {0}.

Action:
See error message.

JPS-08517
System audit definition already exists.

Category:
Security

Cause:
System audit definition already exists.

Action:
See error message.

JPS-08518
Failed to create system audit definition. Reason: {0}.

Category:
Security

Cause:
Failed to create system audit definition. Reason: {0}.

Action:
See error message.

JPS-08519
Error in creating filter tree. Reason: {0}.

Category:
Security

Cause:
Error in creating filter tree. Reason: {0}.

Action:
See error message.

JPS-08520
Audit definition {0} is invalid.

Category:
Security

Cause:
Audit definition {0} is invalid.

Action:
See error message.

JPS-08521
Attribute mapping table {0} for component type {1} is invalid.

Category:
Security

Cause:
Attribute mapping table {0} for component type {1} is invalid.

Action:
See error message.

JPS-08522
Filter config {0} for component type {1} is invalid.

Category:
Security

Cause:
Filter config {0} for component type {1} is invalid.

Action:
See error message.

JPS-08523
Component type value {0} is invalid.

Category:
Security

Cause:
Component type value {0} is invalid.

Action:
See error message.

JPS-08524
System definition {0} is invalid.

Category:
Security

Cause:
System definition {0} is invalid.

Action:
See error message.

JPS-08525
Audit definition for component type {0} not found.

Category:
Security

Cause:
Audit definition for component type {0} not found.

Action:
See error message.

JPS-08526
XLF for component type {0} not found.

Category:
Security

Cause:
XLF for component type {0} not found.

Action:
See error message.

JPS-08527
Attribute mapping table for component type {0} not found.

Category:
Security

Cause:
Attribute mapping table for component type {0} not found.

Action:
See error message.

JPS-08528
Filter config for component type {0} not found.

Category:
Security

Cause:
Filter config for component type {0} not found.

Action:
See error message.

JPS-08529
Generic attribute groups not found.

Category:
Security

Cause:
Generic attribute groups not found.

Action:
See error message.

JPS-08530
Failed to search audit definition in audit store. Reason: {0}.

Category:
Configuration

Cause:
Failed to search audit definition in audit store. Reason: {0}.

Action:
Ensure that the audit store configuration for audit service are correct in jps-config.xml.

JPS-08531
Failed to create audit metadata in audit store. Reason: {0}.

Category:
Configuration

Cause:
Failed to create audit metadata in audit store. Reason: {0}.

Action:
Ensure that the audit store configuration for audit service are correct in jps-config.xml.

JPS-08532
Audit definition "{0}" in destination store does not match the one in source store.

Category:
Configuration

Cause:
Audit definition "{0}" in destination store does not match the one in source store.

Action:
See error message.

JPS-08533
Component XLF for audit definition "{0}" in destination store does not match the one in source store.

Category:
Configuration

Cause:
Component XLF for audit definition "{0}" in destination store does not match the one in source store.

Action:
See error message.

JPS-08534
Generic attribute groups in destination store do not match those in source store.

Category:
Configuration

Cause:
Generic attribute groups in destination store does not match the one in source store.

Action:
See error message.

JPS-08535
Attribute group "{0}" in destination store does not match the one in source store.

Category:
Configuration

Cause:
Attribute group "{0}" in destination store does not match the one in source store.

Action:
See error message.

JPS-08536
Audit filter config for audit definition "{0}" in destination store does not match the one in source store.

Category:
Configuration

Cause:
Audit filter config for audit definition "{0}" in destination store does not match the one in source store.

Action:
See error message.

JPS-08537
Attribute mapping table for audit definition "{0}" in destination store does not match the one in source store.

Category:
Configuration

Cause:
Attribute mapping table for audit definition "{0}" in destination store does not match the one in source store.

Action:
See error message.

JPS-08538
Event definitions for audit definition "{0}" in destination store does not match the one in source store.

Category:
Configuration

Cause:
Event definitions for audit definition "{0}" in destination store does not match the one in source store.

Action:
See error message.

JPS-08539
Event category "{0}" in destination store does not match the one in source store.

Category:
Configuration

Cause:
Event category "{0}" in destination store does not match the one in source store.

Action:
See error message.

JPS-08540
Level list for audit definition "{0}" in destination store does not match the one in source store.

Category:
Configuration

Cause:
Level list for audit definition "{0}" in destination store does not match the one in source store.

Action:
See error message.

JPS-08541
Filter preset definition list for audit definition "{0}" in destination store does not match the one in source store.

Category:
Configuration

Cause:
Filter preset definition list for audit definition "{0}" in destination store does not match the one in source store.

Action:
See error message.

JPS-08542
Attribute "{0}" in attribute group "{1}" in the destination store does not match the one in source store.

Category:
Configuration

Cause:
Attribute "{0}" in attribute group "{1}" in the destination store does not match the one in source store.

Action:
See error message.

JPS-08543
Custom filter preset definition in filter config of audit definition "{0}" in the destination store does not match the one in source store.

Category:
Configuration

Cause:
Custom filter preset definition in filter config of audit definition "{0}" in the destination store does not match the one in source store.

Action:
See error message.

JPS-08544
Failed to remove component definition "{0}". Reason: {1}.

Category:
Security

Cause:
Failed to remove component definition "{0}". Reason: {1}.

Action:
See error message.

JPS-08545
Failed to update component definition "{0}". Reason: {1}.

Category:
Security

Cause:
Failed to update component definition "{0}". Reason: {1}.

Action:
See error message.

JPS-08546
Filter preset definition "{0}" in filter config of audit definition "{1}" in the destination store does not match the one in source store.

Category:
Configuration

Cause:
Filter preset definition "{0}" in filter config of audit definition "{1}" in the destination store does not match the one in source store.

Action:
See error message.

JPS-08547
Filter category "{0}" of filter preset definition "{1}" in filter config of audit definition "{2}" in the destination store does not match the one in source store.

Category:
Configuration

Cause:
Filter category "{0}" of filter preset definition "{1}" in filter config of audit definition "{2}" in the destination store does not match the one in source store.

Action:
See error message.

JPS-08548
Cannot register to audit service for component "{0}".

Category:
Security

Cause:
Cannot register component definition "{0}" to audit service. Reason {1}.

Action:
See error message.

JPS-08549
Audit registration service not available.

Category:
Security

Cause:
Audit registration service not available.

Action:
See error message.

JPS-08550
Audit loader startup failed. Cause: "{0}".

Category:
Security

Cause:
Audit loader startup failed.

Action:
See error message.

JPS-08551
Failed to upgrade audit event definition due to incompatible data mapping. Component type: "{0}".

Category:
Security

Cause:
Failed to upgrade audit event definition due to incompatible data mapping. Component type: "{0}".

Action:
See error message.

JPS-08552
Upgrade audit event definition with incompatible data mapping. Component type: "{0}".

Category:
Security

Cause:
Upgrade audit event definition with incompatible data mapping. Component type: "{0}".

Action:
See error message.

JPS-08553
Failed to load opss_audit_registration.xml. Reason "{0}".

Category:
Security

Cause:
Failed to load opss_audit_registration.xml, Reason "{0}".

Action:
See error message.

JPS-08554
Failed to register Component type "{0}" due to malformed version number in event definition.

Category:
Security

Cause:
Failed to register Component type "{0}" due to malformed version number in event definition.

Action:
See error message.

JPS-08555
During provisioning operations, subscriptions will not be accepted

Category:
Security

Cause:

Action:

JPS-08556
Component type value null is invalid.

Category:
Security

Cause:
Component type value null is invalid.

Action:
Use the appropriate componentType while doing registration of component to AuditStore

JPS-08557
Component events definition file is invalid. Reason - "{0}".

Category:
Security

Cause:
Component events definition file is invalid. Reason - "{0}".

Action:
Correct the events definition file based on reason

JPS-08558
Failed to rollback audit registration failure for component "{0}" , Reason "{1}".

Category:
Security

Cause:
Failed to rollback audit registration failure for component "{0}" , Reason "{1}".

Action:
See error message.

JPS-08559
No matching system event definition for EventRef "{0}" , regarded as a custom Event.

Category:
Security

Cause:
No matching system event definition for EventRef "{0}" , regarded as a custom Event.

Action:
See error message.

JPS-09000
Resource type {0} already in use for {1}.

Category:
Security

Cause:
Resource type was already in use.

Action:
Use a different resource type name.

JPS-09001
Resource matching class name is missing. A subtype must not have its own matching algorithm.

Category:
Security

Cause:
Resource matching class name was missing.

Action:
A subtype must not have its own matching algorithm.

JPS-09002
The parameter {0} of type {1} does not exist.

Category:
Security

Cause:
This parameter did not exist.

Action:
See the log files for more details.

JPS-09003
For the parameter {0} more than expected values found for the Application name:{1}, Policy Domain:{2}, Query Parameter:{3}, Actual results: {4}

Category:
Security

Cause:
More then expected values for given parameter found.

Action:
See the log files for more details.

JPS-09004
For type {0} the modification is not allowed for {1}.

Category:
Security

Cause:
Modify operation was not allowed.

Action:
See the log files for more details.

JPS-09005
For the parameter {0} the given value {1} is invalid.

Category:
Security

Cause:
The value for the given parameter was invalid.

Action:
Provide the valid value for the given paramter.

JPS-09006
Resource {0} already in use for {1}.

Category:
Security

Cause:
Resource was already in use.

Action:
Use a different resource name.

JPS-09007
RoleCategory {0} cannot be deleted

Category:
Security

Cause:
The role category is referenced by one or more application roles.

Action:
Modify the application role(s) definition that reference this role category by removing the role category for the application role.

JPS-09008
Application policy for application {0} does not exist.

Category:
Security

Cause:
Application policy did not exist.

Action:
The application policy must exist. Check the policy store.

JPS-09009
Only limited set of properties are supported for resource action search. See the documentation for more details.

Category:
Security

Cause:
The property user to search resource action was invalid.

Action:
Only limited set of properties are supported for resource action search. See the documentation for more details.

JPS-09010
Cannot create permission set {0} with a non existent resource type {1}.

Category:
Security

Cause:
Permission set could not be created without resource type.

Action:
Resource type must be pre-defined to create the permission set.

JPS-09011
Cannot create permission set {0} with a non existent resource {1}.

Category:
Security

Cause:
Permission set could not be created without resource.

Action:
Resource must be pre-defined to create the permission set.

JPS-09012
Search value cannot be null. It can be null only if MATCHER is ANY.

Category:
Security

Cause:
Search value was null. It could be null only if MATCHER is ANY.

Action:
Verify the search value for the given query.

JPS-09013
This application roles {0} does not belong to this application {1}.

Category:
Security

Cause:
This application role did not belong to this application.

Action:
Ensure this application role belongs to this application.

JPS-09014
The application role {0} cannot have null name or unique name for the application {1}.

Category:
Security

Cause:
The name or unique name of this application role was null or invalid.

Action:
Ensure the name or unique name of this application role is valid.

JPS-09015
Application role does not exist in current application.

Category:
Security

Cause:
Application role was not found in current application.

Action:
Ensure the application role belongs to this application.

JPS-09016
Unknown policy store service type {0}.

Category:
Configuration

Cause:
Unknown policy store service type {0}.

Action:
Correct the policy store configuration.

JPS-09017
Policy entry {0} cannot be found.

Category:
Configuration

Cause:
Policy entry {0} cannot be found.

Action:
Correct the policy entry.

JPS-09018
Policy object {0} cannot be found.

Category:
Configuration

Cause:
Policy object {0} cannot be found.

Action:
Correct the policy object.

JPS-09019
{0} could not be cached.

Category:
Configuration

Cause:
{0} did not be cached.

Action:
Ensure the Resource has valid actions.

JPS-09020
Principal entry class "{0}", name "{1}" cannot be created.

Category:
Configuration

Cause:
Principal entry class "{0}", name "{1}" cannot be created.

Action:
Ensure that the principal entry class is correct and entry value is valid.

JPS-09021
Permission entry class "{0}", target "{1}", action "{2}" cannot be created.

Category:
Configuration

Cause:
Permission entry class "{0}", target "{1}", action "{2}" cannot be created.

Action:
Ensure that the permission entry class is correct and entry value is valid.

JPS-09022
Resource entry type "{0}", resource "{1}" cannot be created.

Category:
Configuration

Cause:
Resource entry type "{0}", resource "{1}" cannot be created.

Action:
Ensure that the resource entry class is correct and entry value is valid.

JPS-09023
Resource type entry name "{0}", matcher class "{1}", provider "{2}" cannot be created.

Category:
Configuration

Cause:
Resource type entry name "{0}", matcher class "{1}", provider "{2}" cannot be created.

Action:
Ensure that the resource type entry class is correct and entry value is valid.

JPS-09024
Resource action entry type "{0}", name "{1}" cannot be created.

Category:
Configuration

Cause:
Resource action entry type "{0}", name "{1}" cannot be created.

Action:
Ensure that the resource action entry class is correct and entry value is valid.

JPS-09025
Permission set entry (name: "{0}", actions: "{1}") cannot be created.

Category:
Configuration

Cause:
Permissionset entry name "{0}", actions "{1}" cannot be created.

Action:
Ensure that the permissionset entry class is correct and entry value is valid.

JPS-09026
Role category entry name "{0}" cannot be created.

Category:
Configuration

Cause:
Role category entry name "{0}" cannot be created.

Action:
Ensure that the role category entry class is correct and entry value is valid.

JPS-09027
Grantee DN was missing for principal {0}.

Category:
Configuration

Cause:
Grantee DN was missing for principal {0}.

Action:
Check principal value.

JPS-09028
Failed to get permission for principal {0}. Reason: {1}.

Category:
Configuration

Cause:
Failed to get permission for principal {0}. Reason: {1}.

Action:
Check principal value.

JPS-09029
Total Time to getPermissions in the Application {0} with {1} number of Grantees is: {2} ms.

Category:
Configuration

Cause:
Total Time to getPermissions in the Application {0} with {1} number of Grantees is: {2} ms.

Action:
Check log for details.

JPS-09030
Code signer data {0} cannot be migrated due to limitation in the destination policy store.

Category:
Configuration

Cause:
Code signer data {0} cannot be migrated due to limitation in the destination policy store.

Action:
Check log for details.

JPS-09031
Failed to read java policies for Application: {0}. Reason: {1}.

Category:
Configuration

Cause:
Failed to read java policies for Application: {0}. Reason: {1}.

Action:
Check log for details.

JPS-09032
Only one of permission array {0} and permission entry list {1} can be null or non-null.

Category:
Configuration

Cause:
Only one of permission array {0} and permission entry list {1} can be null/non-null.

Action:
Ensure one of permission array or permission entry list values is null or non-null.

JPS-09033
No grantee found for grantee entry {0}.

Category:
Configuration

Cause:
No grantee found for grantee entry {0}.

Action:
Ensure the grantee exist in the policy store.

JPS-09034
Modification on single-value attribute {0} but contains multiple attribute values.

Category:
Configuration

Cause:
Modification on single-value attribute {0} but contains multiple attribute values.

Action:
Check modification details.

JPS-09035
Failed to create DN for {0}. Reason: {1}.

Category:
Configuration

Cause:
Failed to create DN for {0}. Reason: {1}.

Action:
Check DN name.

JPS-09036
Failed to read JACC policy {0}. Reason: {0}.

Category:
Configuration

Cause:
Failed to read JACC policy {0}. Reason: {0}.

Action:
Check LDAP configuration to resolve this error.

JPS-09037
No application DN found for name {0} under farm {1}.

Category:
Configuration

Cause:
No application DN found for name {0} under farm {1}.

Action:
Check DN name.

JPS-09038
Resource type {0} does not exist for resource {1}

Category:
Security

Cause:
This resource type does not exist.

Action:
Provide a valid resource type.

JPS-09041
Expression component provided for RuleExpressionEntry must not be null.

Category:
Programmatic

Cause:
Expression component provided for RuleExpressionEntry must not be null.

Action:
Check value of ExpressionComponent.

JPS-09042
Invalid expression component provided to RuleExpressionEntry.

Category:
Programmatic

Cause:
Invalid expression component provided to RuleExpressionEntry.

Action:
Check value of ExpressionComponent.

JPS-09043
Function entry for an expression must not be null.

Category:
Programmatic

Cause:
Function entry for an expression must not be null.

Action:
Check value of FunctionEntry.

JPS-09044
Expression component of type {0} not supported.

Category:
Programmatic

Cause:
Expression component of type {0} not supported.

Action:
Check value of ExpressionComponent.

JPS-09045
Minimum number of input parameters must be less than maximum number of input parameters

Category:
Programmatic

Cause:
Minimum number of input parameters must be less than maximum number of input parameters

Action:
Check parameters to constructor of VarArgsInfo.

JPS-09046
The Matcher {0} in the search query is invalid

Category:
Programmatic

Cause:
The matcher in the search query is invalid

Action:
Provide a valid Search Matcher in the query.

JPS-09047
The Property {0} in the search query is invalid

Category:
Programmatic

Cause:
The search property in the query is invalid

Action:
Provide a valid Search property in the query.

JPS-09048
The search value is invalid

Category:
Programmatic

Cause:
The search value in the query is invalid

Action:
Provide a valid Search value in the query.

JPS-09049
Null value provided for {0}

Category:
Programmatic

Cause:
Invalid value provided to DataType object.

Action:
Provide a non-null value

JPS-09050
Host name {0} is invalid for DNS name

Category:
Programmatic

Cause:
Invalid value provided as DNS host.

Action:
Provide a valid value

JPS-09051
Invalid data. Lower DNS port {0} is greater than higher port {1}.

Category:
Programmatic

Cause:
Lower port is greater than upper range.

Action:
Provide a valid value

JPS-09052
Unknown format, can not parse valid date from string {0}.

Category:
Programmatic

Cause:
Unknown format for date string.

Action:
Provide a valid value

JPS-09053
Invalid string {0} for fractional seconds.

Category:
Programmatic

Cause:
Invalid string for fractional seconds.

Action:
Provide a valid value

JPS-09054
Invalid string {0} for hour offset.

Category:
Programmatic

Cause:
Invalid string for hour offset.

Action:
Provide a valid value

JPS-09055
Invalid string {0} for minute offset.

Category:
Programmatic

Cause:
Invalid string for minute offset.

Action:
Provide a valid value

JPS-09056
Negative value {0} not allowed.

Category:
Programmatic

Cause:
Negative value not aloowed.

Action:
Provide a valid value

JPS-09057
Invalid string {0} for dayTimeDuration. Cannot parse.

Category:
Programmatic

Cause:
Invalid string format for dayTimeDuration

Action:
Provide a valid value

JPS-09058
Invalid string {0} for RFC822 name.

Category:
Programmatic

Cause:
RFC822Name cannot end with @.

Action:
Provide a valid value

JPS-09059
Invalid string {0} for RFC822 domain.

Category:
Programmatic

Cause:
Invvalid RFC822 domain name.

Action:
Provide a valid value

JPS-09060
Invalid string {0} for yearMonthDuration.

Category:
Programmatic

Cause:
Invalid string format for yearMonthDuration

Action:
Provide a valid value

JPS-09061
Invalid string {0} for OpssTime, must be a number.

Category:
Programmatic

Cause:
Invalid string for time field, must be a number.

Action:
Provide a valid value

JPS-09062
Invalid value {0}, must be between lower range {1} and upper range {2}.

Category:
Programmatic

Cause:
Value provided for data type not in required range.

Action:
Provide a valid value

JPS-09063
Invalid inputted Hex Binary value {0}.

Category:
Programmatic

Cause:
Invalid value provided for OpssHexBinary data type.

Action:
Provide a valid value

JPS-09064
Invalid extension manager, cannot be used to find constraint attributes and functions.

Category:
Programmatic

Cause:
Internal error: invalid extension manager cannot be used to find constraint attributes or functions.

Action:
Provide correct function.

JPS-09400
Attribute key cannot be null.

Category:
Requests/Responses

Cause:
Attribute key was null.

Action:
Provide a valid attribute key.

JPS-09401
Name of attribute key cannot be null.

Category:
Requests/Responses

Cause:
Name of attribute key was null.

Action:
Provide a valid name of attribute key.

JPS-09402
Attribute service instance not found in the default context.

Category:
Configuration

Cause:
Attribute service instance not found in the default JpsContext.

Action:
Configure an attribute service instance in the default JpsContext.

JPS-09500
Template name is not initialized, please follow the document for method execution order

Category:
Requests/Responses

Cause:
Template name is not initialized.

Action:
Ensure that execution order is followed as per document

JPS-09501
Either template name or target store or target key or credential object is passed as NULL, {0} is not inserted

Category:
Requests/Responses

Cause:
Either template name or target store or target key or credential objcet is passed as NULL, corresponding credential/key object is not inserted

Action:
Ensure that all the parameters are passed to insert credential/key object

JPS-09502
Error occurred when initializing security artifacts. Reason {0}

Category:
Requests/Responses

Cause:
Security Artifact initialization failed

Action:
Check the logs

JPS-09503
Error occurred when cleaning the environment, please clean it manually

Category:
Requests/Responses

Cause:
Error occurred while cleaning the environment

Action:
Please clean it manually

JPS-09504
Error occurred when processing credentials for template {0}. Reason {1}

Category:
Requests/Responses

Cause:
Failed while processing credentials

Action:
Check the logs

JPS-09505
Error occurred when processing keys for template {0}. Reason {1}.

Category:
Requests/Responses

Cause:
Failed while processing keys

Action:
Check the logs

JPS-09506
Error occurred when commiting changes, calling abort method to clean up the environment

Category:
Requests/Responses

Cause:
Failed while commiting changes

Action:
Please check the logs

JPS-09507
No templates are processed, please call processXXX() methods

Category:
Requests/Responses

Cause:
No templates are processed, please call processXXX() methods

Action:
Please call processXXX() methods before calling end() method

JPS-09508
No artifacts found for template {0}

Category:
Requests/Responses

Cause:
No templates specified in component-security-info.xml file

Action:
Please add new template in component-security-info.xml file

JPS-09509
No processing mode specified for template {0}

Category:
Requests/Responses

Cause:
No processing mode specified for a template

Action:
Please add processing mode for a template in component-security-info.xml file

JPS-09510
No credentials found for template {0}

Category:
Requests/Responses

Cause:
No credentials are available to seed into OPSS security store for template {0}

Action:
Please check the logs or corresponding credential data file in template

JPS-09511
Not able to instantiate credential store object for credential store {0}

Category:
Requests/Responses

Cause:
Scratch directory credential store initialization failed

Action:
Please check the logs

JPS-09512
Not able to instantiate key store service object for key stores {0}

Category:
Requests/Responses

Cause:
Scratch directory key store initialization failed

Action:
Please check the logs

JPS-09513
Not able to get the handle for bootstrap cwallet.sso {0}

Category:
Requests/Responses

Cause:
Not able to get the handle for bootstrap wallet

Action:
Please check the logs

JPS-09514
Credential already exist for map {0} and key {1}

Category:
Requests/Responses

Cause:
Credentials already exist in the Opss CredentialStore Implementation

Action:
Pass credentials with unique map and key name

JPS-09515
CIE CredentialsInfo object should not be null

Category:
Requests/Responses

Cause:
Passed CIE CredentialStoreInfo object is NULL

Action:
Please pass valid CIE credential object

JPS-09516
CIE KeystoreInfo object should not be null

Category:
Requests/Responses

Cause:
Passed CIE KeystoresInfo object is NULL

Action:
Please pass valid CIE key store object

JPS-09517
CIE PrivateKeyInfo object should not be null

Category:
Requests/Responses

Cause:
Passed CIE PrivateKeyInfo object is NULL

Action:
Please pass valid CIE private key object

JPS-09518
Alias '"{0}'" already exist in key store {1}

Category:
Requests/Responses

Cause:
Alias already exist in the Opss key store Implementation

Action:
Please key object with unique alias

JPS-09519
Error occurred when processing audit data for template {0}. Reason {1}

Category:
Requests/Responses

Cause:
Failed while processing audit data

Action:
Check the logs

JPS-09520
Error occurred when processing authorization data for template {0}. Reason {1}.

Category:
Requests/Responses

Cause:
Failed while processing authorization data

Action:
Check the logs

JPS-09521
More than one application stripe {0} found in authorization data file {1}.

Category:
Requests/Responses

Cause:
More than one application stripe in authorization data file

Action:
Ensure that the authorization file does not have more than one application stripe

JPS-09522
Authorization data file {0} is not present.

Category:
Requests/Responses

Cause:
No authorization data file found.

Action:
Verify if the file is present

JPS-09523
No keys found for template {0}

Category:
Requests/Responses

Cause:
No keys are available to seed into OPSS security store for template {0}

Action:
Please check the logs or corresponding keystore data file in template

JPS-09524
More than one component types found in audit store data file {0} for template {1}.

Category:
Requests/Responses

Cause:
More than one component types in audit store data file

Action:
Ensure that the audit store file does not have more than one component type

JPS-09525
Invalid target store is configured in component-security-info.xml. Target store could only be 'SEED' or 'CUSTOMER'.

Category:
Requests/Responses

Cause:
Invalid target store is configured in component-security-info.xml.

Action:
Ensure that target store is 'SEED' or 'CUSTOMER'.

JPS-09600
File {0} is cannot be found. Check if the specified file is expected in the specified location.

Category:
Configuration

Cause:
File {0} cannot be found.

Action:
Check if the specified file exists and accessible in the specified location.

JPS-09601
The value "{0}" is invalid for {1}.

Category:
Configuration

Cause:
An invalid value was provided for this configuration.

Action:
Provide the correct value.

JPS-09602
Fail to find default JPS Context in {0}.

Category:
Configuration

Cause:
Fail to find default JPS Context in the jps-config.xml.

Action:
Check content of jps-config.xml.

JPS-09603
SecurityContext.getSharedSecretStore and getSharedSecretStorePassword return inconsistent values.

Category:
Configuration

Cause:
SecurityContext.getSharedSecretStore and getSharedSecretStorePassword return inconsistent values.

Action:
Both shared secret store name and password are required for configuring a domain with shared database security store.

JPS-09604
JDBC Information {0} is missing for configuring security store to database.

Category:
Configuration

Cause:
JDBC Information is missing for configuring security store to database.

Action:
Check if all required jdbc information is supplied.

JPS-09605
Fail to find JPS Context with id {0} in {1}.

Category:
Configuration

Cause:
Fail to find the specific JPS Context in the jps-config.xml.

Action:
Check content of jps-config.xml.

JPS-09606
Error encountered while importing encryption key in shared database security store.

Category:
Configuration

Cause:
Error encoutered while seeding encryption key in shared database security store.

Action:
Check if encryption key is exported and imported properly.

JPS-09607
OpssSecurityConfiguration is in invalid state.

Category:
Configuration

Cause:
OpssSecurityConfiguration is in invalid state, it has not been initialized properly

Action:
If creating expanded domain, check if database is up and all the required datasource information are provided.

JPS-09608
OpssSecurityConfiguration is in invalid state, start method is not invoked prior to other methods.

Category:
Configuration

Cause:
OpssSecurityConfiguration is in invalid state - start() method is not invoked by CIE prior to other methods

Action:
Check if CIE is invoking OpssSecurityConfiguration in proper order.

JPS-09609
Failed to initialize OPSS security context based on SecurityContext object from CIE.

Category:
Configuration

Cause:
Failed to initialize OPSS security context based on SecurityConext object passed from CIE.

Action:
Check the logs.

JPS-09610
Error during updating audit loader repositoryType. Exception {0}

Category:
Configuration

Cause:
Failed to update audit loader repository type to DB.

Action:
Check the logs.

JPS-09611
Error updating audit loader credential in bootstrap wallet. Exception {0}

Category:
Configuration

Cause:
Failed to add audit loader credentials to bootstrap wallet

Action:
Check the logs.

JPS-09612
JDBC password for {0} is missing for configuring security store to database.

Category:
Configuration

Cause:
JDBC password is missing for configuring security store to database.

Action:
Check if jdbc password is supplied.

JPS-09613
JDBC username for {0} is missing for configuring security store to database.

Category:
Configuration

Cause:
JDBC username is missing for configuring security store to database.

Action:
Check if jdbc username is supplied.

JPS-09614
The supplied password for property {0} is invalid.

Category:
Configuration

Cause:
The supplied password for property {0} is invalid.

Action:
Please provide valid password.

JPS-09615
Update jps configuration file(s) failed for service {0}. Exception {1}

Category:
Configuration

Cause:
Update jps configuration file(s) failed for service {0}.

Action:
Check log file for errors.

JPS-09616
The schema {0} is already in use for security store(s). Please create a new schema.

Category:
Configuration

Cause:
The schema {0} is already in use for security store(s).

Action:
Please create a new schema.

JPS-09617
Failed to create a domain with shared security store because no security store was found in the database schema {0}.

Category:
Configuration

Cause:
Failed to create a domain with shared security store because no security store was found in the database schema {0}.

Action:
Please check if a security store is configured properly for the database schema.

JPS-09618
Data migration failed for configurator {0}

Category:
Configuration

Cause:
Failed to migrate data for configurator {0}.

Action:
Please check the logs and check if a security store is configured properly for the database schema.

JPS-09619
Jps test service failed for configurator

Category:
Configuration

Cause:
Jps test service failed for configurator.

Action:
Please check the logs and check if a security store is configured properly for the database schema.

JPS-09620
Failed to rollback data.

Category:
Configuration

Cause:
Failed to rollback data.

Action:
Please check the logs

JPS-09621
No entry found for artifact type {0} in component-security-info.xml file of template {1}.

Category:
Requests/Responses

Cause:
Artifact is not registered in component-security-info.xml file of template, but artifact data is present as part of template.

Action:
Please register missing artifact in component-security-info.xml file

JPS-09622
Error during configuring DB security store. Exception {0}.

Category:
Configuration

Cause:
Error occured during configuring DB security store.

Action:
Check the logs

JPS-09623
Error during updating JPS configuration in shared DB security store. Exception {0}.

Category:
Configuration

Cause:
Error updating JPS configuration in shared DB security store.

Action:
Check the logs

JPS-09624
JDBC database name for {0} is missing for configuring security store to database.

Category:
Configuration

Cause:
JDBC database name is missing for configuring security store to database.

Action:
Check if jdbc database is supplied.

JPS-09625
Jps test service completed for configurator.

Category:
Configuration

Cause:
Jps test service completed for configurator.

Action:
No action required.

JPS-09626
Rolling back of data for configurator is completed.

Category:
Configuration

Cause:
Rolling back of data for configurator is completed.

Action:
No action required

JPS-09627
Trying to rollback data for configurator.

Category:
Configuration

Cause:
Trying to rollback data for configurator.

Action:
No action required

JPS-09630
Failed to seed MDS credential to bootstrap cwallet file with specified key/map {0}.

Category:
Configuration

Cause:
Failed to seed MDS credential to bootstrap cwallet file.

Action:
Check the logs

JPS-09631
Failed to create tenant config profile {0} in MDS.

Category:
Configuration

Cause:
Failed to create tenant config profiles in MDS.

Action:
Check the logs

JPS-09632
More than one config-security-file.xml are round in templates.

Category:
Configuration

Cause:
More than one config-security-file.xml in templates are found.

Action:
Check the logs

JPS-09633
Start to provisioning partition {0} with OPSS resource group. Parameters: {1}.

Category:
Configuration

Cause:
Start to provisioning a partition with OPSS resource group.

Action:
No action required

JPS-09634
Rollback partition provisioning.

Category:
Configuration

Cause:
Rollback partition provisioning.

Action:
No action required

JPS-09635
Partition provisioning with OPSS resource group is completed.

Category:
Configuration

Cause:
Successfully provisioning a partition with OPSS resource group.

Action:
No action required

JPS-10000
There was an internal error in the policy store.

Category:
Security

Cause:
The opearion is not allowed for multivalued attribute.

Action:
The opearion is not allowed for multivalued attribute.Supply a valid opearion

JPS-10001
Exception happened while decoding value: {0}.

Category:
Security

Cause:
The encoding format is not correct.

Action:
Check encoding format of String value.

JPS-10002
Container is not ready. Reason: {0}.

Category:
Security

Cause:
Container is not ready.

Action:
Wait for container to start up successfully.

JPS-10003
Null search value is not allowed, unless the matcher is ANY.

Category:
Security

Cause:
Query value is null but the matcher is not ANY.

Action:
Do not use null query value if the matcher is not ANY.

JPS-10004
The search value {0} is invalid.

Category:
Security

Cause:
Query value is invalid.

Action:
Use an valid query value.

JPS-10005
Access denied. {0}

Category:
Security

Cause:
Access to policy store is denied.

Action:
Do not perform such operation on policy store.

JPS-10050
The application {0} cannot be found at runtime due to {1}.

Category:
Security

Cause:
Corresponding runtime application does not exist.

Action:
Check if policy is properly distributed.

JPS-10051
Policy object "{0}" already exists in application policy "{1}".

Category:
Security

Cause:
Policy object with same name exists in this application policy.

Action:
Try a different name.

JPS-10052
The list of runtime events is NULL.

Category:
Security

Cause:
The list of runtime events is NULL

Action:
Please contact the security administrator.

JPS-10053
The runtime events is NULL.

Category:
Security

Cause:
The runtime event is NULL

Action:
Please contact the security administrator.

JPS-10100
The policy domain "{0}" does not exist.

Category:
Security

Cause:
The policy domain does not exist

Action:
Check the policy domain name.

JPS-10102
The policy domain "{0}" already exists.

Category:
Security

Cause:
The policy domain exists

Action:
Create a policy domain with a different name.

JPS-10151
Application role {0} does not exist

Category:
Security

Cause:
The application role does not exist.

Action:
Provide correct application role.

JPS-10152
Application Role {0} is used.

Category:
Security

Cause:
Application Role is used.

Action:
Remove the objects which use this application role.

JPS-10153
Application role {0} does not belong to current application.

Category:
Security

Cause:
Application role does not belong to current application policy.

Action:
Modify the application role with application role manager from correct application policy.

JPS-10154
Class {0} is not supported.

Category:
Security

Cause:
The principal class specified is not supported.

Action:
Provide correct principal class.

JPS-10155
The application role attribute {0} is not supported for app role search.

Category:
Security

Cause:
The application role attribute specified is not supported.

Action:
Provide supported attribute.

JPS-10156
Error occurred while fetching the application role {0}.

Category:
Security

Cause:
The internal error occured while fetching the application role.

Action:
Refer to the log files for details and correct the error.

JPS-10157
More than one results found for given Application role:{0}, Application name {1}, query:{2} and Actual result: {3}.

Category:
Security

Cause:
More than one results found for application name.

Action:
Refer to the log files for details and correct the error.

JPS-10158
Invalid parameter.

Category:
Security

Cause:
Invalid parameter value.

Action:
Please check the values are of required type.

JPS-10159
Application Role {0} has an invalid unique name

Category:
Security

Cause:
Application role has an invalid unique name

Action:
See the log files for more details.

JPS-10160
The Application role {0} does not belong to application. The application role dn {1} and unique name {2} are not matching.

Category:
Security

Cause:
The Application role does not belong to application contex.

Action:
See the log files for more details.

JPS-10161
Internal error- More than one grantee entries found.

Category:
Security

Cause:
Internal error- More than one grantee entries found.

Action:
See the log files for more details.

JPS-10162
Grantee DN was missing

Category:
Security

Cause:
Grantee DN was missing

Action:
See the log files for more details.

JPS-10163
Internal error while revoking the permissions. Number of permissions to revoke (or delete) {0} : though only {1} permission(s) would be revoked (or deleted) if this operation were to proceed

Category:
Security

Cause:
Internal error while revoking the permissions.

Action:
See the log files for more details.

JPS-10164
Only one of permission list and permission entry list can be null/non-null.

Category:
Security

Cause:
Only one of permission list and permission entry list can be null/non-null

Action:
See the log files for more details.

JPS-10165
MATCHER.ANY not allowed for this kind of search operation

Category:
Security

Cause:
MATCHER.ANY not allowed for this kind of search operation

Action:
Search is not allowed for the MATCHER.ANY

JPS-10166
Error occurred during performing the operation {0}.

Category:
Security

Cause:
Error occured during performing the operation.

Action:
See the log files for more details.

JPS-10167
Obligation does not exist for the policy domain {0}.

Category:
Security

Cause:
Obligation does not exist for the policy domain {0}.

Action:
See the log files for more details.

JPS-10168
Error occurred while preparing the principal in {0} method of {1} class : {2}. In standalone mode, weblogic specific jars should not be in classpath. Please check the classpath and try again.

Category:
Security

Cause:
Fail to resolve principal.

Action:
Check classpath which may contain weblogic specific jars.

JPS-10169
Default SystemAdminRole should be granted to at least one principal.

Category:
Security

Cause:
Revoking last member of default admin role SystemAdmin

Action:
Keep at least one member of default admin role SystemAdmin

JPS-10200
Administration role {0} already exists

Category:
Security

Cause:
Cannot have two administration roles with the same name.

Action:
Provide a new name to the administration role.

JPS-10201
Administration role {0} does not exist

Category:
Security

Cause:
Administration role is not found.

Action:
Check the administration role name.

JPS-10202
Administration role {0} is used

Category:
Security

Cause:
Administration role is used.

Action:
Remove administration role members first.

JPS-10203
Administration role {0} does not belong to current context

Category:
Security

Cause:
Administration role does not belong to current context.

Action:
Use it in correct context.

JPS-10204
Cannot create admin role with default name {0}

Category:
Security

Cause:
Cannot create admin role with reserved name.

Action:
Use another name for admin role.

JPS-10205
Cannot delete default admin role {0}

Category:
Security

Cause:
Cannot delete default admin role.

Action:
Check the admin role name for deletion.

JPS-10206
Cannot grant {0}, {1} to admin role because its super admin role has no such privilege

Category:
Security

Cause:
Cannot grant privileges to admin role whose super role has not.

Action:
Check the admin resource action to grant.

JPS-10207
Admin resource {0} is not for this scope {1}

Category:
Security

Cause:
This admin resource is not for this scope

Action:
Check the admin resource to grant.

JPS-10208
Cannot change rights of default admin role {0}

Category:
Security

Cause:
Cannot change righs of default admin role for a scope

Action:
Check the admin role name.

JPS-10209
The value for the SEARCH_PROPERTY.PRINCIPAL does implement the java.security.Principal interface. It is of type "{0}".

Category:
Security

Cause:
The search by value is not an instance of java.security.Principal

Action:
Supply an object of type java.security.Principal

JPS-10210
The value for the SEARCH_PROPERTY.PRINCIPAL_NAME is not of type java.lang.String. It is of type "{0}".

Category:
Security

Cause:
The search by value is not an instance of java.lang.String

Action:
Supply an object of type java.lang.String

JPS-10211
Administration role cannot have more than one grantee for parameter Application:{0}, policy Domain:{1}, Query Parameter:{2}, Actual results:{3}.

Category:
Security

Cause:
The admin role cannot have more than one grantee entry.

Action:
Check only one grantee entry available to admin role.

JPS-10250
Resource type reference should not be null.

Category:
Security

Cause:
The parameter resource type reference is null.

Action:
Use a valid object.

JPS-10251
The resource type reference is invalid.

Category:
Security

Cause:
The current resource type reference is invalid.

Action:
Use a valid resource type reference.

JPS-10252
The resource type "{0}" already exists.

Category:
Security

Cause:
The resource type has existed.

Action:
Make sure the resource type does not exist.

JPS-10253
The super resource type {0} does not exist.

Category:
Security

Cause:
The resource type is referring an invalid super resource type.

Action:
Make sure the super resource type exist.

JPS-10254
The resource type {0} should not have its own matcher since it has super type.

Category:
Security

Cause:
The resource type has both its own matching algorithm and super type.

Action:
Remove matching algorithm if the resource type should have super type. Otherwise, remove super type.

JPS-10255
Resource type search context should not be null.

Category:
Security

Cause:
The resource type context could not be gotten.

Action:
Make sure the application policy is available.

JPS-10256
Could not get an available data manager.

Category:
Security

Cause:
The data manager is invalid.

Action:
Make sure policy store and related configuration are correct.

JPS-10257
The modification operator {0} is invalid.

Category:
Security

Cause:
The operator in ModificationItem is invalid.

Action:
Make sure the operation is one of DirContext.ADD_ATTRIBUTE, DirContext.REPLACE_ATTRIBUTE and DirContext.REMOVE_ATTRIBUTE.

JPS-10258
The property name {0} is unknown.

Category:
Security

Cause:
The attribute ID in ModificationItem is undefined.

Action:
Make sure the attribute ID is a valid one.

JPS-10259
The name of resource type could not be modified.

Category:
Security

Cause:
Resource type name could not be modified.

Action:
Do not put resource type name in ModificationItem.

JPS-10260
The super type of resource type could not be modified.

Category:
Security

Cause:
The super type of resource type could not be modified.

Action:
Do not put super type in ModificationItem.

JPS-10261
The matching algorithm of resource type could not be modified.

Category:
Security

Cause:
The matching algorithm of resource type could not be modified.

Action:
Do not put matching algorithm in ModificationItem

JPS-10262
The action delimiter of resource type could not be modified.

Category:
Security

Cause:
The action delimiter of resource type could not be modified.

Action:
Do not put action delimiter in ModificationItem.

JPS-10263
The operation REPLACE_ATTRIBUTE could not be used to the allowed actions of resource type.

Category:
Security

Cause:
The operation REPLACE_ATTRIBUTE could not be used to the allowed actions of resource type.

Action:
Use REMOVE_ATTRIBUTE and ADD_ATTRIBUTE in ModificationItem.

JPS-10264
The property {0} of resource type is single, could not have more than one value.

Category:
Security

Cause:
The property could not have more than one value.

Action:
First remove the existing value before adding new one.

JPS-10265
Could not add or replace the property {0} since there is no value provided.

Category:
Security

Cause:
There is no value provided when trying to add or replace an property.

Action:
Provide the new value.

JPS-10266
The value data type of property {0} should be String.

Category:
Security

Cause:
The value data type of property is not String.

Action:
Use a String object as value.

JPS-10267
The resource type {0} does not exist.

Category:
Security

Cause:
The resource type does not exist.

Action:
Make sure the resource type exist.

JPS-10268
The resource type {0} is in use, could not be deleted.

Category:
Security

Cause:
The resource type could not be deleted without cascade since it is in use.

Action:
Cascade delete it or first remove all referring objects.

JPS-10269
The operation REPLACE_ATTRIBUTE could not be used to the resource type attribute

Category:
Security

Cause:
The operation REPLACE_ATTRIBUTE could not be used to the resource type attribute

Action:
Use REMOVE_ATTRIBUTE and ADD_ATTRIBUTE in ModificationItem.

JPS-10270
The resource type attribute {0} is used in policy(-ies) and can not be deleted.

Category:
Security

Cause:
The resource type attribute being deleted was used in one or morepolicies and could not be deleted.

Action:
Before deleting the resource attribute, make sure it is not used.

JPS-10271
The resource matcher class of resource type {0} could not be modified to {1}.

Category:
Security

Cause:
The resource type matcher class was changed while modifying.

Action:
Keep matcher class unchanged.

JPS-10272
Permission Class not found in the classpath: {0}

Category:
Security

Cause:
The permission class was not found in the class path.

Action:
Make sure that the permission class is part of the class path for the program.

JPS-10273
Permission class expected to be either oracle.security.jps.ResourcePermission or extending oracle.security.jps.AbstractTypedPermission but found {0} Resource Type: {1} is sharing permission class with Resource Type: {2}

Category:
Security

Cause:
The Permission class is not either ResourcePermission or Abstracted Permission

Action:
The Permission class for the resource type must be a Resource permission

JPS-10274
Permission should be associated with a Resource Type. Permission Name: {0}

Category:
Security

Cause:
The permission should have a resource type associated with it

Action:
Make sure that the permission has a resource type associated with it

JPS-10275
Resource Type Matcher Class and Permissions do not match. {0} and {1} do not match

Category:
Security

Cause:
Resource Type Matcher Class and Permissions do not match.

Action:
Make sure that the Matcher Class and Permissions match.

JPS-10276
Cannot determine the Resource Type from the permission {0}

Category:
Security

Cause:
Cannot determine the Resource Type from the permission.

Action:
Make sure that there is a resource type associated with the permission class

JPS-10277
Allowed attributes can not be modified.

Category:
Security

Cause:
Allowed attributes can not be modified.

Action:
Make sure not modifying allowed attributes

JPS-10278
Requested modification to the resource type {0} is not allowed.

Category:
Security

Cause:
Requested modification to the resource type is not allowed.

Action:
Make sure not to make certain type of changes to the resource type when it is used by resources

JPS-10279
The custom resource matcher class of resource type {0} could not be modified to {1}.

Category:
Security

Cause:
The custom resource matcher class was changed while modifying the resource type.

Action:
Keep custom resource matcher class unchanged.

JPS-10280
The resource attribute {0} does not exist in the resource type {1}.

Category:
Security

Cause:
The resource attribute does not exist in the resource type.

Action:
Check all the valid resource attributes in the resource type.

JPS-10400
Resource reference should not be null.

Category:
Security

Cause:
The parameter resource reference is null.

Action:
Use a valid object.

JPS-10401
The resource reference is invalid.

Category:
Security

Cause:
The current resource reference is invalid.

Action:
Use a valid resource reference.

JPS-10402
The resource {0} does not exist.

Category:
Security

Cause:
The resource does not exist.

Action:
Make sure the resource exist.

JPS-10403
Could not get an available data manager.

Category:
Security

Cause:
The data manager is invalid.

Action:
Make sure policy store and related configuration are correct.

JPS-10404
The resource type {0} does not exist.

Category:
Security

Cause:
The resource type does not exist.

Action:
Make sure the resource type exist.

JPS-10405
The resource "{0}" with type "{1}" already exists in current application policy.

Category:
Security

Cause:
The resource to be created has existed.

Action:
Make sure the resource does not exist.

JPS-10406
The modification operator {0} is invalid.

Category:
Security

Cause:
The operator in ModificationItem is invalid.

Action:
Make sure the operation is one of DirContext.ADD_ATTRIBUTE, DirContext.REPLACE_ATTRIBUTE and DirContext.REMOVE_ATTRIBUTE.

JPS-10407
The property name {0} is unknown.

Category:
Security

Cause:
The attribute ID in ModificationItem is undefined.

Action:
Make sure the attribute ID is a valid one.

JPS-10408
The name and type of resource could not be modified.

Category:
Security

Cause:
The name and type of resource could not be modified.

Action:
Do not put resource name and type in ModificationItem.

JPS-10409
The property {0} of resource is single, could not have more than one value.

Category:
Security

Cause:
The property could not have more than one value.

Action:
First remove the existing value before adding new one.

JPS-10410
Could not add or replace the property {0} since there is no value provided.

Category:
Security

Cause:
There is no value provided when trying to add or replace an property.

Action:
Provide the new value.

JPS-10411
The resource {0} is in use, could not be deleted.

Category:
Security

Cause:
The resource could not be deleted without cascade since it is in use.

Action:
Cascade delete it or first remove all referring objects.

JPS-10412
The resource attribute {0} already exists in the current entry.

Category:
Security

Cause:
The resource attribute could not be added since it already exists.

Action:
Remove duplicate resource attributes.

JPS-10413
The resource action {0} already exists in the current entry.

Category:
Security

Cause:
The resource action could not be added since it already exists.

Action:
Remove duplicate resource actions

JPS-10414
The resource attribute {0} could not be deleted since it does not exist.

Category:
Security

Cause:
The resource attribute could not be deleted since it does not exist.

Action:
Check if the resource attribute exists.

JPS-10415
The resource action {0} could not be deleted since it does not exist.

Category:
Security

Cause:
The resource action could not be deleted since it does not exist.

Action:
Check if the resource action exists

JPS-10416
Resource {0} does not belong to the context.

Category:
Security

Cause:
The resource does not belong to current context

Action:
Pass in correct resource.

JPS-10417
Resource query across different resource type is not allowed.

Category:
Security

Cause:
Resource query across different resource type is not allowed

Action:
Pass in correct query parameter.

JPS-10418
Cannot delete a resource that has one more child resources.

Category:
Security

Cause:
Can not detele a resource that has one or more child resources

Action:
Delete all child resources and then try again.

JPS-10419
Resource hierarchy type change is not allowed.

Category:
Security

Cause:
Resource hierarchy type change is not allowed.

Action:
Check the resource hierarchy type

JPS-10420
Resource name must begin with the resource name delimiter.

Category:
Security

Cause:
Resource name must begin with the resource name delimiter

Action:
Add resource name delimiter in the begining of the resource name.

JPS-10421
The given all action key word exists in actions.

Category:
Security

Cause:
The given all action value already exists

Action:
Check the input all action value and check for duplicate values.

JPS-10422
The resource attribute {0} is used in policy(-ies) and can not be deleted.

Category:
Security

Cause:
The resource attribute is used in policy(-ies) and can not be deleted.

Action:
Before deleting the resource attribute, make sure it is not used.

JPS-10423
The action {0} is used by the {1} and can not be deleted.

Category:
Security

Cause:
The action is used by the permissionSet/permission and can not be deleted.

Action:
Check if the action is used in any PermissionSet/Permission before deleting.

JPS-10424
The resourceType {0} of hierarchy type is invalid as its parent is null.

Category:
Security

Cause:
The heirarical resourcetype's parent is null.

Action:
Make sure to provide a valid name for the heirarical resourcetype

JPS-10425
The resource attribute {0} contains duplicate value {1}.

Category:
Security

Cause:
The resource attribute already contains this value.

Action:
Remove duplicate resource attributes values.

JPS-10426
Cannot set all actions keyword for resource type with non-null matcher class.

Category:
Security

Cause:
All actions keyword cannot be set to resource type with matcher class

Action:
Do not set all actions keyword for a resource type with a matcher class.

JPS-10427
The resource name expression "{0}" is not a valid Java regular expression.

Category:
Security

Cause:
Regular expression provided for resource name expression is invalid.

Action:
Check that the resource name expression is a valid Java regular expression.

JPS-10428
The resource {0} of type {1} does not exist.

Category:
Security

Cause:
The resource of the resource type does not exist.

Action:
Make sure the resource of the resource type exists.

JPS-10429
The value data type of property {0} should be String and not {1}.

Category:
Security

Cause:
The value data type of property is not String.

Action:
Use a String object as value.

JPS-10430
The Resource name {0} has an invalid format

Category:
Security

Cause:
Too many delimiters in the resurce name

Action:
Limit the number of delimiters in the beginning and middle of resource name to one.

JPS-10431
Wrong isSingle property for the attribute {0}; expected {1}, but {2}.

Category:
Security

Cause:
Wrong isSingle property of resource attribute

Action:
Ensure isSingle property of the attribute in resource is the same as the definiton in resource type

JPS-10432
Wrong DataType property for the attribute {0}; expected {1}, but {2}.

Category:
Security

Cause:
Wrong DataType property of resource attribute

Action:
Ensure DataType property of the attribute on resource is the same as the definition in resource type

JPS-10451
Permission set {0} does not belong to the context.

Category:
Security

Cause:
The permission set does not belong to current context

Action:
Pass in correct permission set.

JPS-10452
Permission set {0} has ResourceActionsEntry with null ResourceEntry and null ResourceNameExpression.

Category:
Security

Cause:
Both ResourceEntry and Resource name expression of ResourceActionsEntry is null

Action:
Pass in correct ResourceActionsEntry.

JPS-10454
No resources or actions have been identified by the permission set.

Category:
Security

Cause:
No resources or actions have been identified by the permissionset.

Action:
Ensure that the permission set is created with valid resource actions.

JPS-10455
Type of the resource does not define matcher java permission class.

Category:
Security

Cause:
Resource is not protected by a Java Permission.

Action:
Ensure that the permission set is created with valid resource object.

JPS-10456
ResourceExpression and ResourceAction cannot be specified at the same time.

Category:
Security

Cause:
ResourceExpression and ResourceAction cannot be specified at the same time.

Action:
PermissionSet ResourceAction should contain either Resource expression or ResoruceEntry.

JPS-10457
Not able to perform operation due to invalid parameter. Cause: "{0}".

Category:
Security

Cause:
Not able to perform operation due to invalid parameter. Cause: {0}.

Action:
Ensure that the operation is called with valid parameters.

JPS-10458
ResourceExpression and ResourceAction cannot be null at the same time.

Category:
Security

Cause:
ResourceExpression and ResourceAction cannot be null at the same time.

Action:
PermissionSet ResourceAction should contain either Resource expression or ResoruceEntry.

JPS-10459
The modified permission set {0} contains resources of multiple resource types. It is not permitted as there is policy(-ies) that references that permission set and uses resource attributes.

Category:
Security

Cause:
The modified permission set contained resources of multiple resource types. It was not permitted if there was a policy that referenced that permission set and used resource attributes.

Action:
Fix the permission set or modify the policy(-ies).

JPS-10460
The permission set search query {0} is not supported

Category:
Security

Cause:
The permission set search query is not supported.

Action:
Use supported query scenario.

JPS-10463
Requested actions: " {0} " are not a subset of valid actions: " {1}" for the given resource: " {2} " and type: " {3} ".

Category:
Security

Cause:
Invalid resource actions for the given resource.

Action:
Ensure that the actions in the resource-actions are a valid subset of the actions defined by the resource type.

JPS-10464
Error occurred while getting the permission set entry for permission set search query {0}.

Category:
Security

Cause:
Error occured while getting the permission set entry for permission set search query.

Action:
See the log files for more details.

JPS-10465
Permission set {0} has ResourceActionsEntry with null expression in ResourceNameExpression.

Category:
Security

Cause:
Expression in ResourceNameExpression of ResourceActionsEntry is null

Action:
Pass in correct ResourceActionsEntry with non-null Resource name expression.

JPS-10466
Resource {0} has no Resource Actions, but Resource Type {1} has resource actions.

Category:
Security

Cause:
Empty resource actions for the given Resource, but Resource type has actions.

Action:
Ensure that the actions in the resource-actions are not null or empty since the resource type has actions.

JPS-10467
Permission set {0} has ResourceActionsEntry with null expression in ResourceNameExpression.

Category:
Security

Cause:
Expression in ResourceNameExpression of ResourceActionsEntry is null

Action:
Pass in correct ResourceActionsEntry with non-null Resource name expression.

JPS-10468
Duplicate permission " {0} " in policy store.

Category:
Security

Cause:
Duplicate permission in policy store.

Action:
Check the policy store and ensure that there is no duplicate permission.

JPS-10469
Cannot remove all the ResourceActionsEntrys in PermissionSet.

Category:
Security

Cause:
Try to remove all the ResourceActionsEntrys in existing PermissionSet.

Action:
Check the updated resource actions, make sure PermissionSet does not have up empty resource actions.

JPS-10470
The resource type name "{0}", does not match the resourceType in the encoded target name: "{1}". Permission class is "{2}"

Category:
Security

Cause:
Invalid resource type in permission target.

Action:
Refer to the log files for details.

JPS-10471
Resource type is missing in the target name: "{0}", for permission: "{1}"

Category:
Security

Cause:
Resource type missing in permission target.

Action:
Refer to the log files for details.

JPS-10472
Target "{0}" is missing the prefix "=resourceName=". Unable to determine the resource name for permission: "{1}"

Category:
Security

Cause:
Target name missing in permission target.

Action:
Refer to the log files for details.

JPS-10473
The target name "{0}" is invalid. Should start with "{1}"

Category:
Security

Cause:
Target name encoding is not correct.

Action:
Refer to the log files for details.

JPS-10474
The parameter: "{0}", value: "{1}" cannot be null

Category:
Security

Cause:
Permission target is null.

Action:
Refer to the log files for details.

JPS-10475
The permission actions: "{0}" are not a subset of valid actions defined in resource type: "{1}"

Category:
Security

Cause:
Permission actions do not match with valid resource type actions.

Action:
Refer to the log files for details.

JPS-10476
The resource name can not be null

Category:
Security

Cause:
Invalid resource name in permission target.

Action:
Refer to the log files for details.

JPS-10500
The target policy, {0}, does not exist.

Category:
Security

Cause:
The policy object does not exist.

Action:
Check if the target policy exists.

JPS-10501
Policy query contains unrecognizable information.

Category:
Security

Cause:
Policy query contains unrecognizable information.

Action:
Check the policy query object.

JPS-10502
Policy rule information is missing.

Category:
Security

Cause:
Policy rule information is missing.

Action:
Check if policy rule information exists in policy repository.

JPS-10503
Obligation information is missing.

Category:
Security

Cause:
Obligation information is missing.

Action:
Check if obligation information exists in policy repository.

JPS-10504
Permission set information is missing.

Category:
Security

Cause:
Permission set information is missing.

Action:
Check if permission set information exists in policy repository.

JPS-10505
Grantee information is missing.

Category:
Security

Cause:
Grantee information is missing.

Action:
Check if grantee information exists in policy repository.

JPS-10506
The policy rule, {0}, does not exist.

Category:
Security

Cause:
The policy rule does not exist.

Action:
Check the policy rule name passed in.

JPS-10507
The condition string is in wrong format, {0}.

Category:
Security

Cause:
Condition string is in wrong format.

Action:
Check condition string in policy repository.

JPS-10508
Policy condition contains an unknown function, {0}.

Category:
Security

Cause:
Policy condition contains an unknown function.

Action:
Check condition string in policy repository.

JPS-10509
Policy condition parsing error.

Category:
Security

Cause:
Policy condition parsing error.

Action:
Check condition string in policy repository.

JPS-10510
The expression, {0}, is unknown.

Category:
Security

Cause:
The policy expression is unknown.

Action:
Check condition string in policy repository.

JPS-10511
The data type, {0}, is unknown.

Category:
Security

Cause:
The data type is unknown

Action:
Check condition string in policy repository.

JPS-10512
A ResourceActionsEntry should contain either resource entry or resource name expression.

Category:
Security

Cause:
The ResourceActionsEntry object does not contain resource infomation.

Action:
Check ResourceActionsEntry passed in.

JPS-10513
The search value type {0} is not supported for {1}.

Category:
Security

Cause:
Query criteria type does not support.

Action:
Pass in a correct query value.

JPS-10514
Cannot add PermissionSet to PolicyEntry if it has ResourceType.

Category:
Security

Cause:
Resource type is already defined in PolicyEntry.

Action:
clear resource type of PolicyEntry before adding PermissionSetEntry.

JPS-10515
Cannot set ResourceType to PolicyEntry if it has PermissionSet.

Category:
Security

Cause:
Permission Set is already defined in PolicyEntry.

Action:
clear Permission Set of PolicyEntry before setting Resource Type.

JPS-10516
Cannot add Rule if there is rule already in PolicyEntry

Category:
Security

Cause:
Add rule to policy when the policy already has rule.

Action:
Delete existing rule before adding new rule to policy.

JPS-10517
Delete rule not existing in PolicyEntry

Category:
Security

Cause:
rule does not belong to the PolicyEntry.

Action:
Check the rule before deleting rule from PolicyEntry.

JPS-10518
Delete permission set not existing in PolicyEntry

Category:
Security

Cause:
permission set does not belong to the PolicyEntry.

Action:
Check the permission set before deleting permission set from PolicyEntry.

JPS-10519
Delete obligation not existing in PolicyEntry

Category:
Security

Cause:
obligation does not belong to the PolicyEntry.

Action:
Check the obligation before deleting obligation from PolicyEntry.

JPS-10520
Delete Principal not existing in PolicyEntry

Category:
Security

Cause:
principal does not belong to the PolicyEntry.

Action:
Check the principal before deleting principal from PolicyEntry.

JPS-10521
The obligation {0} already exists.

Category:
Security

Cause:
The obligation already exists in the policy entry.

Action:
Check ObligationEntry passed in.

JPS-10522
The parameters passed in is invalid, we expect {0}, but {1} is passed in.

Category:
Security

Cause:
The parameter passed in the function is not valid.

Action:
Pass in correct parameters.

JPS-10523
The function return type is invalid, we expect OpssBoolean, but {0} is passed in.

Category:
Security

Cause:
The return type of the function is not valid.

Action:
Pass in a function with OpssBoolean return type.

JPS-10524
The query with search property {0}, comparator type {1} and matcher {2} is not supported.

Category:
Security

Cause:
Such query is not supported.

Action:
Pass in a supported query value.

JPS-10525
The attribute assignment {0} could not be added since it already exists.

Category:
Security

Cause:
The attribute assignment could not be added since it already exists.

Action:
Remove duplicate attribute assignments.

JPS-10526
The permission set {0} could not be added since it already exists.

Category:
Security

Cause:
The permission set could not be added since it already exists.

Action:
Remove duplicate permission sets.

JPS-10527
The principal {0} could not be added since it already exists.

Category:
Security

Cause:
The principal could not be added since it already exists.

Action:
Remove duplicate principals.

JPS-10528
The Policy {0} referenced multiple resource types and resource attribute is used in policy condition or obligation.

Category:
Security

Cause:
Policies that used resource attributes in their conditions or obligations could not refrence one or more permission sets that contain resources of multiple types.

Action:
Split the policy to reference only one resource type in each policy.

JPS-10529
The resource attribute {0} used in policy condition or obligation is invalid resource attribute of type {1}.

Category:
Security

Cause:
The resource attribute used in policy condition was invalid for the referenced resource type

Action:
Fix the policy condition to use only valid attributes for the given resource type.

JPS-10530
Cannot create a policy {0} with AdminRole(s) {1}.

Category:
Security

Cause:
Cannot create a policy with AdminRoleEntry(s).

Action:
Remove the AdminRole principals from the principal list.

JPS-10531
Cannot grant permission to AdminRole(s) {0}.

Category:
Security

Cause:
Cannot grant permission to AdminRoleEntry(s).

Action:
Remove the AdminRole principals from the principal list.

JPS-10532
Cannot grant AdminRole {0} to another AdminRole {1}.

Category:
Security

Cause:
Cannot grant AdminRole to another AdminRole.

Action:
Change to grant AdminRole to either enterprise role or user.

JPS-10533
Cannot revoke AdminRole {0} from another AdminRole {1}.

Category:
Security

Cause:
Cannot revoke AdminRole from another AdminRole.

Action:
Change to revoke AdminRole from either enterprise role or user.

JPS-10534
Cannot grant AdminRole {0} to an AppRole {1}.

Category:
Security

Cause:
Cannot grant AdminRole to an AppRole.

Action:
Change to grant AdminRole to either enterprise role or user.

JPS-10535
Cannot revoke AdminRole {0} from an AppRole {1}.

Category:
Security

Cause:
Cannot revoke AdminRole from an AppRole.

Action:
Change to revoke AdminRole from either enterprise role or user.

JPS-10536
AdminRole {0} cannot be managed outside of the AdminManager.

Category:
Security

Cause:
AdminRole cannot be managed outside of AdminManager.

Action:
Use AdminManager for all AdminRole related administrative tasks.

JPS-10537
Cannot modify grant permission to AdminRole(s) {0}.

Category:
Security

Cause:
Cannot modify grant permission to AdminRoleEntry(s).

Action:
Remove the AdminRole principals from the principal list.

JPS-10538
Cannot revoke permission from AdminRole(s) {0}.

Category:
Security

Cause:
Cannot revoke permission from AdminRoleEntry(s).

Action:
Remove the AdminRole principals from the principal list.

JPS-10539
Basic policy cannot have {0} information.

Category:
Security

Cause:
Basic policy cannot have {0} information.

Action:
Remove the information from basic policy.

JPS-10540
Basic policy cannot have ResourceActionsEntry without ResourceEntry.

Category:
Security

Cause:
Basic policy cannot have ResourceActionsEntry without ResourceEntry.

Action:
Use ResourceActionsEntry with ResourceEntry for basic policy.

JPS-10541
Basic policy cannot use Resource {0} without Resource Matcher Class.

Category:
Security

Cause:
Basic policy cannot use Resource {0} without Resource Matcher Class.

Action:
Use Resource with Resource Matcher Class for basic policy.

JPS-10542
Default TransformerFactory cannot be located.

Category:
Security

Cause:
The TransformerFactory cannot be loaded

Action:
Check the environment

JPS-10543
Failed to retrieve Transformer.

Category:
Security

Cause:
The TransformerFactory cannot generate a Transformer.

Action:
Check the environment

JPS-10544
The policy "{0}" already exists.

Category:
Security

Cause:
The role policy object exists.

Action:
Create a role policy with a different name.

JPS-10545
The application role {0} could not be added since it already exists.

Category:
Security

Cause:
The application role could not be added since it already exists.

Action:
Remove duplicate application role.

JPS-10546
The resource {0}, {1} could not be added since it already exists.

Category:
Security

Cause:
The resource could not be added since it already exists.

Action:
Remove duplicate resource.

JPS-10547
The resource name expression {0}, {1} could not be added since it already exists.

Category:
Security

Cause:
The resource name expression could not be added since it already exists.

Action:
Remove duplicate resource name expression.

JPS-10548
The policy rule {0} already exists.

Category:
Security

Cause:
The policy rule already exists.

Action:
Create policy rule with different name.

JPS-10549
The policy rule {0} is in use, could not be deleted.

Category:
Security

Cause:
The policy rule could not be deleted without cascade since it is in use.

Action:
Cascade delete it or first remove all referring objects.

JPS-10550
Attribute "{0}" already exists

Category:
Security

Cause:
Cannot have two attributes with the same name.

Action:
Provide a new name to the attribute.

JPS-10551
Attribute {0} does not exist

Category:
Security

Cause:
Attribute not found.

Action:
Check the attribute name.

JPS-10552
Attribute {0} is used.

Category:
Security

Cause:
Attribute is already used.

Action:
Remove the objects which use this attribute.

JPS-10553
Attribute {0} does not belong to current application.

Category:
Security

Cause:
Attribute does not belong to current application policy.

Action:
Modify the attribute with extension manager from correct application policy.

JPS-10554
The name of Attribute in policy repository is missing

Category:
Security

Cause:
Attribute in policy store has no name.

Action:
Check the underline policy repository.

JPS-10555
The type of Attribute in policy repository is missing

Category:
Security

Cause:
Attribute in policy store has no type.

Action:
Check the underline policy repository.

JPS-10556
The category of Attribute in policy repository is missing

Category:
Security

Cause:
Attribute in policy store has no category.

Action:
Check the underline policy repository.

JPS-10557
Cannot overwrite a built-in attribute, {0}.

Category:
Security

Cause:
Try to overwrite a built-in attribute.

Action:
Do not overwrite a built-in function.

JPS-10558
Cannot modify a built-in attribute, {0}.

Category:
Security

Cause:
Try to modify a built-in attribute.

Action:
Do not modify a built-in attribute.

JPS-10559
Cannot delete a built-in attribute, {0}.

Category:
Security

Cause:
Try to delete a built-in attribute.

Action:
Do not delete a built-in attribute.

JPS-10581
Cannot overwrite a built-in function, {0}.

Category:
Security

Cause:
Try to overwrite a built-in function.

Action:
Do not overwrite a built-in function.

JPS-10582
The function does not exist, {0}.

Category:
Security

Cause:
The function does not exist.

Action:
Check the function name passed in.

JPS-10583
The function is in use, {0}.

Category:
Security

Cause:
The function is in use.

Action:
Cannot delete a function in use.

JPS-10584
The function is used in some policies, your changes on return type may lead to unpredictable issues.

Category:
Security

Cause:
The function is in use.

Action:
Cannot change return type of a function in use.

JPS-10585
The function is used in some policies, your changes on parameter types may lead to unpredictable issues.

Category:
Security

Cause:
The function is in use.

Action:
Cannot change parameter types of a function in use.

JPS-10586
Cannot modify a built-in function, {0}.

Category:
Security

Cause:
Try to modify a built-in function.

Action:
Do not modify a built-in function.

JPS-10587
Cannot delete a built-in function, {0}.

Category:
Security

Cause:
Try to delete a built-in function.

Action:
Do not delete a built-in function.

JPS-10588
The function "{0}" already exists.

Category:
Security

Cause:
The function exists.

Action:
Create a function with a different name.

JPS-10589
Cascade delete is not supported.

Category:
Security

Cause:
Cascade delete not supported.

Action:
Set the cascade delete parameter to false.

JPS-10590
Cannot find the function entry for function name {0}.

Category:
Security

Cause:
Cannot find the function entry for function name.

Action:
Check function entry in policy repository.

JPS-10591
Cannot find the expression type for expression {0}.

Category:
Security

Cause:
Cannot find the expression type for the expression.

Action:
Check expression in policy repository.

JPS-10592
Operation {1} is not allowed for multi valued attribute {0}

Category:
Security

Cause:
The category of Attribute is Invalid.

Action:
The category of Attribute is Invalid. Supply a valid Attribute category

JPS-10600
Failed to initialize PD instance.

Category:
Security

Cause:
Failed to initialize PD instance.

Action:
Refer to the base exception in logs to resolve the issue.

JPS-10601
Failed to initialize PolicyDistributionManager instance.

Category:
Security

Cause:
Failed to initialize PolicyDistributionManager instance.

Action:
Refer to the base exception in logs to resolve the issue.

JPS-10602
PD has not been initialized.

Category:
Security

Cause:
PD has not been initialized.

Action:
Check if OPSS policy store provider has been initialized successfully.

JPS-10603
FAILURE: Retry {0} failed after {1} times retries due to following exception {2}.

Category:
Security

Cause:
PD operation failed to retry.

Action:
Check connectivity to backend repository.

JPS-10604
The operation is not allowed for non-controlled mode application {0}.

Category:
Security

Cause:
Can not distribute policy for non-controlled policy distribution mode application

Action:
Refer to the log files for details.

JPS-10605
Failed to distribute policy for catch exception.

Category:
Security

Cause:
Distribute policy failed for catch exception

Action:
Refer to the log files for details.

JPS-10606
Failed to distribute policy to PDP {0} for catch exception {1}.

Category:
Security

Cause:
Failed to distribute policy to pdp for catch exception

Action:
Refer to the log files for details.

JPS-10607
Invalid cache key {0} in {1} cache.

Category:
Security

Cause:
Invalid cache key

Action:
Refer to the log files for details.

JPS-10608
Failed to copy files from active directory {0} to update directory {1}.

Category:
Security

Cause:
Failed to copy cache file from active directory to update directory

Action:
Refer to the log files for details.

JPS-10609
Failed to write state.chk file.

Category:
Security

Cause:
Failed to write state.chk file

Action:
Refer to the log files for details.

JPS-10610
Failed to update local cache since distributed payload for application {0} is empty.

Category:
Security

Cause:
Failed to update local cache since distributed payload is empty

Action:
Refer to the log files for details.

JPS-10611
Invalid distribution state {0} in step {1}.

Category:
Security

Cause:
Invalid distribution state

Action:
Refer to the log files for details.

JPS-10612
Local cache file verification failed, so redistribute all binding applications

Category:
Security

Cause:
Failed to verify local cache file, so need to redistribution all binding applications

Action:
Refer to the log files for details.

JPS-10613
Failed to parse PD port number, do not start PD registration web service.

Category:
Security

Cause:
Failed to parse PD port number, do not start PD registration web service.

Action:
Refer to the log files for details.

JPS-10614
Failed to start PD registration web service for catch exception.

Category:
Security

Cause:
Failed to start PD registration web service for catch exception.

Action:
Refer to the log files for details.

JPS-10615
Catch exception.

Category:
Security

Cause:
Catch interrupt exception in start registration service thread.

Action:
Refer to the log files for details.

JPS-10616
Failed to find local host name, do not start PD registration web service.

Category:
Security

Cause:
Failed to find local host name, do not start PD registration web service.

Action:
Refer to the log files for details.

JPS-10617
Failed to start PD push policy web service for catch exception.

Category:
Security

Cause:
Failed to start PD registration web service for catch exception.

Action:
Refer to the log files for details.

JPS-10618
Invalid SSL configuration.

Category:
Security

Cause:
Invalid SSL configuration, please check log for details

Action:
Refer to the log files for details.

JPS-10619
Failed to initialize cipher {0} for local cache encryption/decryption.

Category:
Security

Cause:
Failed to initialize cipher for local cache encryption/decryption.

Action:
Refer to the log files for details.

JPS-10620
Exception reported in registration thread.

Category:
Security

Cause:
Catch interrupt exception in start registration service thread.

Action:
Refer to the log files for details.

JPS-10621
PD Lock not found

Category:
Security

Cause:
PD Lock node not found.

Action:
Refer to the log files for details.

JPS-10622
Invalid PD Lock update time {0}.

Category:
Security

Cause:
Invalid PD Lock update time stamp.

Action:
Refer to the log files for details.

JPS-10623
PD is running in another Admin, please distribute policy after the process finished.

Category:
Security

Cause:
PD is running in another Admin, please distribute policy after the process finished.

Action:
Refer to the log files for details.

JPS-10624
Failed to connect primary server, try secondary server.

Category:
Security

Cause:
Failed to connect primary server, try secondary server.

Action:
Refer to the log files for details.

JPS-10625
Failed to read from the local cache. The cache will be removed. Reason: {0}

Category:
Security

Cause:
Failed to read from the local cache. The cache will be removed.

Action:
Refer to the log files for details.

JPS-10626
Encryption/Decryption of the local cache file using the algorithm {0} is not supported.

Category:
Security

Cause:
The specified algorithm for local cache encryption/decryption is not supported.

Action:
Please check PDP service configuration in jps-config.xml file.

JPS-10627
The key length used to initialize cipher {0} is not valid. Expected key length is {1} bits, but raw key length is {2} bits.

Category:
Security

Cause:
The key length used to initialize cipher is not valid.

Action:
Refer to the log files for details.

JPS-10628
Retry {0} for the {1} times.

Category:
Security

Cause:
Retry {0} for the {1} times.

Action:
No actions are required

JPS-10629
SUCCESS: Retry {0} successfully after {1} times retries.

Category:
Security

Cause:
SUCCESS: Retry {0} successfully after {1} times retries.

Action:
No actions are required

JPS-10630
The default DB policy store is missing for mixed mode.

Category:
Security

Cause:
The default DB policy store is missing for mixed mode.

Action:
Configure one DB policy store instance.

JPS-10631
Failed to distribute policy to Real Application Security Database, target RAS database {0}, exception {1}.

Category:
Security

Cause:
Failed to distribute policy to Real Application Security Database

Action:
Refer to the log files for details.

JPS-10632
Failed to obtain the datasource for Real Application Security Database, target RAS database {0}, exception {1}

Category:
Security

Cause:
Failed to obtain the datasource for Real Application Security Database

Action:
Refer to the log files for details.

JPS-10633
Failed to fetch the information from the intermediate table, target RAS database {0}, exception {1}"

Category:
Security

Cause:
Failed to fetch the information from the intermediate table

Action:
Refer to the log files for details.

JPS-10634
Failed to prepare data for distributing policy to Real Application Security Database, application name {0}, exception {1}.

Category:
Security

Cause:
Failed to prepare data for distributing policy to Real Application Security Database

Action:
Refer to the log files for details.

JPS-10635
Failed to update the intermediate table in the policy store database, target RAS database {0}, exception {1}.

Category:
Security

Cause:
Failed to update the intermediate table in the policy store database

Action:
Refer to the log files for details.

JPS-10636
Incorrect Real Application Security PDP address format.

Category:
Security

Cause:
Incorrect Real Application Security PDP address format

Action:
Refer to the log files for details. The correct format should start with "ras:"

JPS-10700
The value of attribute {0} should be unique

Category:
Security

Cause:
The unique attribute has duplicated values.

Action:
Keep attribute value unique.

JPS-10701
Data Source lookup failure. It is safe to ignore the warning during Websphere server starts up. If you still get the warning after WebSphere server starts up, check your configuration.

Category:
Security

Cause:
Websphere data source lookup failure.

Action:
Safe to ignore during WebSphere starts up.

JPS-10702
The datasource {0} is not found.

Category:
Security

Cause:
Given datasource jndi name is not found.

Action:
Check datasource jndi name.

JPS-10750
Application Policy unique name: "{0}" is invalid

Category:
Security

Cause:
The application policy unique name is invalid

Action:
Refer to the log files for details.

JPS-10751
The version number of Application policy : "{0}" is invalid

Category:
Security

Cause:
The application policy version number is invalid

Action:
Refer to the log files for details.

JPS-10752
The policy entry unique name: "{0}" is invalid

Category:
Security

Cause:
The policy entry unique name is invalid

Action:
Refer to the log files for details.

JPS-10800
The role policy object "{0}" does not exist.

Category:
Security

Cause:
The role policy object does not exist.

Action:
Check if the target role policy exists.

JPS-10801
The role policy object "{0}" already exists.

Category:
Security

Cause:
The policy object exists.

Action:
Create a policy with a different name.

JPS-10802
Application role hierarchy cannot participate in a role mapping policy.

Category:
Security

Cause:
One or more principals in the role mapping policy are of type: ApplicationRole or AnonymousRole or AuthenticatedRole or and AdminRole.

Action:
Identify the principal type in the incomming principals, and ensure only a user or group principal type is supplied.

JPS-10803
At least one of the Resource(s)/Resource Name Expression(s) used in Role Policy are permission based. This is not allowed.

Category:
Security

Cause:
At least one of the Resource(s)/Resource Name Expression(s) used in Role Policy are permission based. This is not allowed.

Action:
Ensure that resource(s)/resource name expression(s) are not permission based.

JPS-10804
The advice {0} already exists.

Category:
Security

Cause:
The advice already exists in the policy entry.

Action:
Check AdviceEntry passed in.

JPS-10850
The SM Config Tool is used to configure the Security Modules for Oracle Entitlements Server Here are the various options that it will accept -smType <java, wls, ws, rmi, was, jboss> -smConfigId <config id of sm is always required> -serverLocation <in case of was, wls, jboss, this is the location of the server> -pdServer OES Admin Server hostName -pdPort SSL Port for OES Admin Server -pdClientPort SSL Port for WLS SM client -serverNodeName - server node name of websphere -serverName - server instance name of websphere -serverUserName - user name of application server -serverPassword - password of application server -prpFileName - path for the prp file used.

Category:
Security

Cause:
When help is asked for

Action:
Help message, no action required

JPS-10851
Please enter a value for {0}:

Category:
Security

Cause:
Prompt Message

Action:
Prompt message, no action required

JPS-10852
Configuring for PDP proxy mode

Category:
Security

Cause:
Prompt Message

Action:
Prompt message, no action required

JPS-10853
Configuring for Controlled Policy Distribution Mode

Category:
Security

Cause:
Prompt Message

Action:
Prompt message, no action required

JPS-10854
Configuring for Direct Connection to the Database Policy Store

Category:
Security

Cause:
Prompt Message

Action:
Prompt message, no action required

JPS-10855
Configuring for Direct Connection to the Ldap Policy Store

Category:
Security

Cause:
Prompt Message

Action:
Prompt message, no action required

JPS-10856
Configuring for Direct Connection to the Derby Policy Store

Category:
Security

Cause:
Prompt Message

Action:
Prompt message, no action required

JPS-10857
Value is missing or corrupt {0}. Please supply an appropriate value.

Category:
Security

Cause:
Error Message

Action:
Please supply the required parameters as specified in the message.

JPS-10858
Security Module configuration is created at: {0}

Category:
Security

Cause:
Prompt Message

Action:
Prompt message, no action required

JPS-10859
Please re-enter a value for {0}:

Category:
Security

Cause:
Prompt Message

Action:
Prompt message, no action required

JPS-10890
sys_obj_q

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10891
Full qualified resource name on which the query is performed: /foo/bar

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10892
sys_subjectroles

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10893
List of unqualified role names granted to user for current request

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10900
The enrollment response is truncated.

Category:
Security

Cause:
Enrollment response is truncated.

Action:
Refer to the log files for details.

JPS-10901
Keystore {0} does not exist.

Category:
Security

Cause:
Keystore {0} does not exist.

Action:
Check the file system.

JPS-10902
Enrollment server error.

Category:
Security

Cause:
Enrollment server error.

Action:
Check enrollment server status.

JPS-10903
Enrollment is proceeded successfully.

Category:
Security

Cause:
Enrollment is proceeded successfully.

Action:
Prompt message, no action required

JPS-10904
Enrollment is not proceeded successfully.

Category:
Security

Cause:
Enrollment is not proceeded successfully.

Action:
Prompt message, no action required

JPS-10905
The program works in console mode only.

Category:
Security

Cause:
The program works in console mode only.

Action:
Prompt message, no action required

JPS-10906
Enter password for {0}:

Category:
Security

Cause:
Enter password for {0}:

Action:
Prompt message, no action required

JPS-10907
Enter password for {0} again:

Category:
Security

Cause:
Enter password for {0} again:

Action:
Prompt message, no action required

JPS-10908
The passwords you inputted do not match.

Category:
Security

Cause:
The passwords you inputted do not match.

Action:
Prompt message, no action required

JPS-10909
Passwords are saved in credential store.

Category:
Security

Cause:
Passwords are saved in credential store.

Action:
Prompt message, no action required

JPS-10910
Passwords are not saved in credential store.

Category:
Security

Cause:
Passwords are not saved in credential store.

Action:
Prompt message, no action required

JPS-10911
{0} is not set.

Category:
Security

Cause:
{0} is not set.

Action:
Prompt message, no action required

JPS-10912
Keystores are initialized successfully.

Category:
Security

Cause:
Keystores are initialized successfully.

Action:
Prompt message, no action required

JPS-10913
Keystores are not initialized successfully.

Category:
Security

Cause:
Keystores are not initialized successfully.

Action:
Prompt message, no action required

JPS-10914
Enter username for {0}:

Category:
Security

Cause:
Enter username for {0}:

Action:
Prompt message, no action required

JPS-10915
Enter credential map name:

Category:
Security

Cause:
Enter credential map name:

Action:
Prompt message, no action required

JPS-10916
Enter credential key name:

Category:
Security

Cause:
Enter credential key name:

Action:
Prompt message, no action required

JPS-10917
Input password can not be null.

Category:
Security

Cause:
The passwords you inputted can not be null.

Action:
Prompt message, no action required

JPS-10920
function: urn:oasis:names:tc:xacml:1.0:function:integer-equal The function returns true if the LHS (left-hand side) matches RHS (right-hand side); If LHS or RHS is a multiple value attribute and the other side is single value attribute, the function returns false; If both LHS and RHS are multiple value attribute, they have the same number of elements and for each element from the list on the left, there exists an element from the list on the right, the function returns true.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10921
function: urn:oasis:names:tc:xacml:1.0:function:date-equal The function returns true if the LHS (left-hand side) matches RHS (right-hand side); If LHS or RHS is a multiple value attribute and the other side is single value attribute, the function returns false; If both LHS and RHS are multiple value attribute, they have the same number of elements and for each element from the list on the left, there exists an element from the list on the right, the function returns true.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10922
function: urn:oasis:names:tc:xacml:1.0:function:time-equal The function returns true if the LHS (left-hand side) matches RHS (right-hand side); If LHS or RHS is a multiple value attribute and the other side is single value attribute, the function returns false; If both LHS and RHS are multiple value attribute, they have the same number of elements and for each element from the list on the left, there exists an element from the list on the right, the function returns true.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10923
function: urn:oasis:names:tc:xacml:1.0:function:string-is-in The function returns true if the LHS (left-hand side) matches one of the values in RHS (right-hand side); LHS should be single-valued. RHS can be single or multi-valued.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10924
function: urn:oasis:names:tc:xacml:1.0:function:integer-is-in The function returns true if the LHS (left-hand side) matches one of the values in RHS (right-hand side); LHS should be single-valued. RHS can be single or multi-valued.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10925
function: urn:oasis:names:tc:xacml:1.0:function:date-is-in The function returns true if the LHS (left-hand side) matches one of the values in RHS (right-hand side); LHS should be single-valued. RHS can be single or multi-valued.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10926
function: urn:oasis:names:tc:xacml:1.0:function:time-is-in The function returns true if the LHS (left-hand side) matches one of the values in RHS (right-hand side); LHS should be single-valued. RHS can be single or multi-valued.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10927
function: urn:oasis:names:tc:xacml:1.0:function:integer-greater-than The function returns true if the value of LHS is greater than RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10928
function: urn:oasis:names:tc:xacml:1.0:function:integer-greater-than-or-equal The function returns true if the value of LHS is greater than or equals to RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10929
function: urn:oasis:names:tc:xacml:1.0:function:integer-less-than The function returns true if the value of LHS is less than RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10930
function: urn:oasis:names:tc:xacml:1.0:function:integer-less-than-or-equal The function returns true if the value of LHS is less than or equals to RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10931
function: urn:oasis:names:tc:xacml:1.0:function:time-greater-than The function returns true if the value of LHS is greater than RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10932
function: urn:oasis:names:tc:xacml:1.0:function:time-greater-than-or-equal The function returns true if the value of LHS is greater than or equals to RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10933
function: urn:oasis:names:tc:xacml:1.0:function:time-less-than The function returns true if the value of LHS is less than RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10934
function: urn:oasis:names:tc:xacml:1.0:function:time-less-than-or-equal The function returns true if the value of LHS is less than or equals to RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10935
function: urn:oasis:names:tc:xacml:1.0:function:date-greater-than The function returns true if the value of LHS is greater than RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10936
function: urn:oasis:names:tc:xacml:1.0:function:date-greater-than-or-equal The function returns true if the value of LHS is greater than or equals to RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10937
function: urn:oasis:names:tc:xacml:1.0:function:date-less-than The function returns true if the value of LHS is less than RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10938
function: urn:oasis:names:tc:xacml:1.0:function:date-less-than-or-equal The function returns true if the value of LHS is less than or equals to RHS. Both LHS and RHS should be single value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10939
function: urn:oasis:names:tc:xacml:1.0:function:string-regexp-match The LHS should be a single-value string type attribute/value. The RHS should be a single value string which complies with Java Regular Expression.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10940
function: urn:oasis:names:tc:xacml:1.0:function:or The function stands for an OR operation between two single-value boolean expressions/values.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10941
function: urn:oasis:names:tc:xacml:1.0:function:and The function stands for an AND operation between two single-value boolean expressions/values.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10942
function: urn:oasis:names:tc:xacml:1.0:function:not The function stands for a NOT operation on a single-value boolean expression/value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10943
function: valid_for_mseconds The function accepts a single integer value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10944
function: valid_for_seconds The function accepts a single integer value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10945
function: valid_for_minutes The function accepts a single integer value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10946
function: valid_for_hours The function accepts a single integer value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10947
function: valid_until_time The function accepts a single time value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10948
function: valid_until_date The function accepts a single date value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10949
function: sys_defined The function accepts a single string value.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10950
current_gmt_time

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10951
current_gmt_date

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10952
sys_subjectgroups

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10953
sys_user

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10954
sys_app

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10955
sys_obj_type

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10956
sys_obj

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10957
sys_privilege

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10958
boolean_equal

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10959
string_equal

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10960
integer_equal

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10961
date_equal

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10962
time_equal

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10963
string_is_in

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10964
integer_is_in

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10965
date_is_in

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10966
time_is_in

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10967
integer_greater_than

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10968
integer_greater_than_or_equal

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10969
integer_less_than

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10970
integer_less_than_or_equal

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10971
time_greater_than

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10972
time_greater_than_or_equal

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10973
time_less_than

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10974
time_less_than_or_equal

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10975
date_greater_than

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10976
date_greater_than_or_equal

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10977
date_less_than

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10978
date_less_than_or_equal

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10979
string_regexp_match

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10980
or

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10981
and

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10982
not

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10983
valid_for_mseconds

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10984
valid_for_seconds

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10985
valid_for_minutes

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10986
valid_for_hours

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10987
valid_until_time

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10988
valid_until_date

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10989
attribute_has_value

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10990
The attribute will be assigned current time value n GMT time zone during evaluation

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10991
The attribute will be assigned current date value n GMT time zone during evaluation

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10992
List of unqualified group names to which user belongs: ["admin", "managers"]

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10993
Current user: unqualified form: system

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10994
Unqualified name of the binding resource for the resource on which the query is performed: admin

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10995
ResourceType on which the query is performed: LibraryResourceType

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10996
Resource on which the query is performed: bar

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10997
Unqualified name of the action on which the resource is being queried.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10998
function: urn:oasis:names:tc:xacml:1.0:function:boolean-equal The function returns true if the LHS (left-hand side) matches RHS (right-hand side);If LHS or RHS is a multiple value attribute and the other side is single value attribute,the function returns false;If both LHS and RHS are multiple value attribute, they have the same number of elements and for each element from the list on the left, there exists an element from the list on the right, the function returns true.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-10999
function: urn:oasis:names:tc:xacml:1.0:function:string-equal The function returns true if the LHS (left-hand side) matches RHS (right-hand side); If LHS or RHS is a multiple value attribute and the other side is single value attribute, the function returns false; If both LHS and RHS are multiple value attribute, they have the same number of elements and for each element from the list on the left, there exists an element from the list on the right, the function returns true.

Category:
Security

Cause:
built-in attribute/function display name and desription

Action:
Prompt message, no action required

JPS-11000
Policy Set member with type: "{0}" and name "{1}" does not exist

Category:
Security

Cause:
The policy set member does not exist in policy store

Action:
Refer to the log files for details.

JPS-11001
Can not delete policy set "{0}" which is referred by other policy set

Category:
Security

Cause:
The policy set to be deleted is referred by other policy set

Action:
Refer to the log files for details.

JPS-11002
Policy set dependency loop could be introduced by modifyPolicySet operation

Category:
Security

Cause:
The policy set depdency could be introduced by modifyPolicySet operation

Action:
Refer to the log files for details.

JPS-11003
Policy set "{0}" does not exist

Category:
Security

Cause:
The policy set entry with specified name does not exist in policy store

Action:
Refer to the log files for details.

JPS-11004
Multiple principal entries provided have principal constraint

Category:
Security

Cause:
Multiple principal entries have principal constraint

Action:
Refer to the log files for details.

JPS-11005
Can not add AllResource to permission set: "{0}"

Category:
Security

Cause:
Adding AllResource to Permission set is not supported

Action:
Refer to the log files for details.

JPS-11006
Adding {0} combiner parameters for {0} "{1}" not referred in this policy set

Category:
Security

Cause:
Adding policy or policy set combiner paramers for policy or policy set not referred in this policy set

Action:
Refer to the log files for details.

JPS-11007
Can not add codesource, principals, resource actions or permission sets to {0}: "{1}" which has XACML3 target

Category:
Security

Cause:
Adding codesource, principals, resource actions or permissin sets to policy, policy set or rule which has XACML3 target

Action:
Refer to the log files for details.

JPS-11008
Can not add XACML3 target to {0}: "{1}" which has codesource, principals, resource actions or permission sets

Category:
Security

Cause:
Adding XACML3 target to policy, policy set or rule which has codesource, principals, resource actions or permissin sets

Action:
Refer to the log files for details.

JPS-11009
Policy set "{0}" already exists

Category:
Security

Cause:
The policy set entry with specified name already exists in the policy store

Action:
Refer to the log files for details.

JPS-12000
No such Configuration Profile "{0}" exists in the system.

Category:
Configuration

Cause:
The specified configuration profile is not registered with configuration service.

Action:
Check the name, or try listing the registered profiles.

JPS-12001
Cannot create ContextConfiguration, A JPS Context with name "{0}" already exists in the system.

Category:
Configuration

Cause:
A jpsContext with the specified contextId exists in the system.

Action:
Use another unique contextId.

JPS-12002
Could not Construct the ConfigurationManagementService: Configuration Context Descriptor NOT FOUND in jps-config.xml or specifies an invalid Configuration serviceInstance descriptor.

Category:
Configuration

Cause:
A jpsContext by the name "ConfigContext" that references a Configuration Service Instance Descriptor is missing from jps-config.xml.

Action:
Check the MultiTenancy Enablement steps and/or scripts.

JPS-12003
Could not Construct ConfigurationManagementService from its Descriptor in jps-config.xml, due to empty/missing configuration data in the Descriptor.

Category:
Configuration

Cause:
The configuration jpsContext does seem to contain a <serviceInstanceRef> pointing to the ConfigurationManagementService instance descriptor.

Action:
Check the MultiTenancy Enablement steps and/or scripts.

JPS-12004
No such JpsContext "{0}" exists in jps-config.xml.

Category:
Configuration

Cause:
A jpsContext with the specified contextId does not exists in the system.

Action:
Check jps-config.xml of the domain.

JPS-12005
A ContextConfiguration with "{0}" "{1}" already exists in the system.

Category:
Data

Cause:
A ContextConfiguration with the specified name already exists.

Action:
Use another unique name.

JPS-12006
No Registered ContextConfiguration with "{0}" "{1}" exists in the system.

Category:
Data

Cause:
The specified configuration profile is not registered with configuration service.

Action:
Check the name, or try listing the registered profiles.

JPS-12007
Cannot delete ContextConfiguration "{0}" in "{1}" state.

Category:
Data

Cause:
A ContextConfiguration in ACTIVE state cannot be deleted.

Action:
DeActivate the context and then try deleting it.

JPS-12008
Cannot DeActivate ContextConfiguration "{0}" as it is in state "{1}".

Category:
Data

Cause:
A ContextConfiguration ACTIVE state (only) can be DeActivated. DeActivation from other states is illegal.

Action:
Make sure the context configuration is ACTIVE and then try deactivating it.

JPS-12009
Cannot Activate ContextConfiguration "{0}" as it is in state "{1}".

Category:
Data

Cause:
A ContextConfiguration must be in COMPLETE or INACTIVE state for Activation to succeed.

Action:
Check to make sure the state of the Context is COMPLETE or INACTIVE.

JPS-12010
Cannot Update ContextConfiguration "{0}" as it is in state "{1}".

Category:
Data

Cause:
A ContextConfiguration must be in CREATED or INACTIVE state before it can be UPDATED.

Action:
Check to make sure the state of the Context is CREATED or INACTIVE. A configuration in COMPLETE or ACTIVE states cannot be updated

JPS-12011
OPSS Runtime Cannot fetch Configuration for context "{0}", The context does not exist or is not in ACTIVE state.

Category:
Data

Cause:
OPSS Runtime failed to fetch the Configuration for the context. Either the context does not exist or is not in ACTIVE state. The Runtime can only view ContextConfigurations in ACTIVE state

Action:
Check to make sure the Context exists and is in ACTIVE state.

JPS-12012
Cannot initialize Configuration Store : One of DataSource/JDBC-URL/FilePath for MetaDataStore should be Configured in the Configuration Service Descriptor.

Category:
Configuration

Cause:
The configuration serviceInstance descriptor does not seem to contain a property for DataSource/JDBC-URL/FilePath for connecting to the Configuration Store.

Action:
Check MultiTenancy enablement steps/scripts.

JPS-12013
File based Configuration Store should be used only for Development and not in Production.

Category:
Configuration

Cause:
File based Configuration Store should be used only for Testing and not in Production.

Action:
Nothing to do if this is a Test Environment, else check Multi-Tenancy enablement steps.

JPS-12014
Map/Key name(s) for Credential required to bind to MetaDataStore with JDBC-URL not configured in the Configuration Service.

Category:
Configuration

Cause:
A Password Credential is required when JDBC-URL is used to connect to the Configuration Store.

Action:
Check to see that the Configuration serviceInstance descriptor contains properties for the Map and Key name of the credential.

JPS-12015
Property JPS_CONFIG_PATH not set for use by PersistenceManager.

Category:
Process

Cause:
Internal Error/Bug: The Configuration Management Service is expected to set a property JPS.CONFIGSERVICE.PATH for use by the PersistenceManager.

Action:
Report Bug on Oracle OPSS with relevant logs.

JPS-12016
Internal Error: Unable to locate ContextConfiguration named "{0}" in the Configuration Profile "{1}".

Category:
Process

Cause:
Internal Error/Bug: The Configuration Service is in a state where it thinks the specified contextId should exist under the specified profileId, but the persisted information in the store does not match the expectation.

Action:
Report Bug on Oracle OPSS with relevant logs.

JPS-12017
Invalid Xpath expression , specified XPath "{0}" does not evaluate to a "{1}".

Category:
Data

Cause:
The XPath expression specified in Customization spec does not point to the intended element in the Configuration Profile document.

Action:
Check the XPath expression against the structure of the configuration Profile being referenced..

JPS-12018
Invalid Location Override in Global Scope. Location Override can be specified for ServiceInstances only.

Category:
Data

Cause:
The Location Override in Customization spec is only applicable to a serviceInstance attribute and cannot be applied to an element in Global Scope.

Action:
Check the XPath expression.

JPS-12019
Cannot apply "{0}" overrides on element of type "{1}", expected an element of type "{2}", check the Element XPath specified in the customization.

Category:
Data

Cause:
The XPath expression specified in Customization spec does not point to the intended element in the Configuration Profile document.

Action:
Check the XPath expression against the structure of the configuration Profile being referenced..

JPS-12020
Cannot modify values of existing ExtendedProperty elements during customization.

Category:
Data

Cause:
Cannot modify values of existing ExtendedProperty elements during customization.

Action:
This is an Unsupported Customization spec, change the customization instructions supplied to the Configuration Management Service.

JPS-12021
Cannot create ContextConfiguration "{0}", No such profile "{1}" exists in the system.

Category:
Data

Cause:
Cannot create ContextConfiguration as the referenced Configuration Profile does not seem to exist.

Action:
Check the name of the specified profile.

JPS-12022
MetaDataObject "{0}" not found. Ensure ContextConfiguration "{1}" exists or first create it.

Category:
Configuration

Cause:
The PersistenceManager is unable to find the MetaDataObject corresponding to the specified contextId.

Action:
Check the name of the context or make sure it is registered with the Configuration Service.

JPS-12023
Mutable MetadataObject "{0}" cannot be obtained from MetadataStore specified since there are pending writes to other MetadataStores. Do flushChanges/cancelChanges on MDSSession to proceed.

Category:
Process

Cause:
Internal Error/Bug : The persistence manager is in a state where it is trying to perform multiple updates to the profile document concurrently.

Action:
Report a Bug on Oracle OPSS with relevant logs.

JPS-12024
A profile with name "{0}" already exists.

Category:
Data

Cause:
A configuration profile with the given name already exists.

Action:
Try using a unique profileId.

JPS-12025
Cannot Delete Profile "{0}" ,Named ContextConfigurations exist under the profile.

Category:
Data

Cause:
A configuration profile which has named ContextConfiguration's referencing it cannot be deleted.

Action:
Try deleting the ContextConfiguration's before attempting to delete the profile.

JPS-12026
No such ContextConfiguration "{0}" exists in the system.

Category:
Data

Cause:
The specified ContextConfiguration is not registered with the Configuration Service.

Action:
Check the name or try listing the registered ContextConfigurations.

JPS-12027
Required PasswordCredential at Map = "{0}",Key = "{1}" was not found in Specified Bootstrap CredentialStore.

Category:
Configuration

Cause:
A required PasswordCredential does not exist at the specified map, and key in the supplied bootstrap credential store.

Action:
Check the bootstrap credential store.

JPS-12028
Malformed jps-config.xml : stale service instance reference "{0}" from JpsContext.

Category:
Configuration

Cause:
The PersistenceManager found a STALE <serviceInstanceRef> that does not exist in the jps-config.xml.

Action:
Check the jps-config.xml of the Profile or the Out-of-the-Box jps-config.xml as appropriate.

JPS-12029
Cannot set Name for ContextConfiguration "{0}" in state "{1}", deactivate it first.

Category:
Data

Cause:
Cannot set contextName for a ContextConfiguration in ACTIVE.

Action:
DeActivate it first and then set a Name for it.

JPS-12030
Cannot setContextName, ConfigurationContext "{0}" is already Named "{1}", unset the Name first.

Category:
Data

Cause:
A ContextConfiguration that is already has a Name cannot be Named again.

Action:
Unset the current Name first and then set a new Name for it.

JPS-12031
Cannot unset Name for ContextConfiguration "{0}" in state "{1}", deactivate it first.

Category:
Data

Cause:
Cannot unset the contextName for a ContextConfiguration in ACTIVE state.

Action:
DeActivate the Context first and then unset the contextName.

JPS-12032
Error in initializing JAXBContext.

Category:
Configuration

Cause:
Internal Error: JAXB context initialization in PersistenceManager Failed.

Action:
Report a Bug on Oracle OPSS with relevant logs.

JPS-12033
Invalid profile jps-config.xml document, does not contain a required element "{0}".

Category:
Configuration

Cause:
Internal Error: the profile document does not contain a mandatory element.

Action:
Check the jps-config.xml that was used as a Configuration Profile.

JPS-12034
MDSPersistenceManager Cannot handle Persistence of Element "{0}".

Category:
Configuration

Cause:
Unsupported operation : The persistence manager configured with the Configuration Service does not handle persistence of the specified element.

Action:
Report a Bug on Oracle OPSS with relevant logs.

JPS-12035
Cannot setContextName for ConfigurationContext "{0}" to Name "{1}", as the Name is already assigned to "{2}".

Category:
Data

Cause:
Names used for ContextConfiguration must be unique, an attempt is being made to set the same Name for more than one ContextConfiguration.

Action:
Use a different unique Name.

JPS-12036
ContextConfiguration "{0}" does not have any name set for it, Naming a ContextConfiguration is mandatory before its configuration STATE can be set to COMPLETE.

Category:
Data

Cause:
An attempt is being made to set the STATE of an Un-Named ContextConfiguraton to COMPLETE.

Action:
Use the setContextName(contextId) method to set a Name.

JPS-12037
Service configuration update done for Configurator.

Category:
Data

Cause:
Service configuration update done for Configurator.

Action:
No action required.

JPS-12038
Failed to check if audit is enabled.

Category:
Configuration

Cause:
Configuration management events logging was not enabled.

Action:
Check the audit configuration to ensure auditing enabled.

JPS-12039
Failed to log audit record.

Category:
Configuration

Cause:
Configuration management audit event logging failed.

Action:
Contact the administrator.

JPS-12040
Missing Property set props.db.1.

Category:
Configuration

Cause:
No Prorperty Set props.db.1 in jps-config.xml

Action:
Check the jps-config.xml.

JPS-12100
The expiry time should be in format {0}

Category:
Configuration

Cause:
Invalid input

Action:
Correct the input.

JPS-12101
The filter value is {0} invalid

Category:
Configuration

Cause:
Invalid input

Action:
Correct the input.

JPS-12102
One of the attributes {0} is undefined

Category:
Configuration

Cause:
Invalid input

Action:
Correct the input.

JPS-12103
Parameter {0} is missing

Category:
Configuration

Cause:
Missing Parameter

Action:
Correct the input.

JPS-12104
Alias {0} did not exist or point to a key

Category:
Configuration

Cause:
Alias did not exist or point to a key

Action:
Correct the input Alias.

JPS-12105
Tenant with id {0} does not exist.

Category:
Configuration

Cause:
Tenant does not exist

Action:
Correct the tenant id.

JPS-12106
The param {0} is invalid - null or empty.

Category:
Configuration

Cause:
Tenant config parameter passed to the API is invalid

Action:
Make sure all parameters are valid

JPS-12107
The param {0} was supplied a restricted value {1}.

Category:
Configuration

Cause:
Tenant config parameter value passed to the API is restricted

Action:
Make sure no restricted values are used

JPS-12109
It is invalid that both of "{0}" and "{1}" are null or empty.

Category:
Configuration

Cause:
Invalid input

Action:
Correct the input, make sure at least one of them is not null or empty

JPS-12110
It is invalid that both of "{0}" and "{1}" have value.

Category:
Configuration

Cause:
Invalid input

Action:
Correct the input, make sure only one of them is not null or empty

JPS-12111
It is invalid that "{0}" is less than "{1}".

Category:
Configuration

Cause:
Invalid input

Action:
Correct the input, make sure the data is reasonable

JPS-12112
It is invalid that "{0}" is less than or equal to "{1}".

Category:
Configuration

Cause:
Invalid input

Action:
Correct the input, make sure the data is reasonable

JPS-12113
Property "{0}" cannot be updated/modified.

Category:
Configuration

Cause:
Unmodifiable property

Action:
Correct the input, make sure the data is reasonable

JPS-12114
Cannot specifify resource name delimiter for non-hierachical resource type

Category:
Configuration

Cause:
Invalid input

Action:
Correct the input, make sure the data is reasonable

JPS-12115
"{0}" is an invalid resource name delimiter character. Valid characters are [/ \ $ # : ; , ! . - _ @ |]

Category:
Configuration

Cause:
Invalid input

Action:
Correct the input, make sure the data is reasonable

JPS-12116
For the attribute "{0}", "{1}" is not a valid value.

Category:
Configuration

Cause:
Invalid input

Action:
Correct the input, make sure the data is reasonable

JPS-12117
Cannot set multiple values to a single value attribute "{0}".

Category:
Configuration

Cause:
Set multi values to a single value attribute

Action:
Correct the input, make sure the data is reasonable

JPS-20000
GlobalPolicy can not be created by MAPI methods

Category:
Programmatic

Cause:
GlobalPolicy can not be created by MAPI methods.

Action:
Set up policy store using reassociation or upgrading

JPS-20001
GlobalPolicy can not be deleted by MAPI methods.

Category:
Programmatic

Cause:
GlobalPolicy can not be deleted by MAPI methods.

Action:
GlobalPolicy is a built-in stripe, can not be deleted

JPS-20002
GlobalPolicy can not be returned from the method.

Category:
Programmatic

Cause:
GlobalPolicy can not be returned from the method.

Action:
Gets GlobalPolicy from the method getGlobalPolicy

JPS-20003
Cannot add global role to application role

Category:
Security

Cause:
Attempted to add a global role {0} to members of an application role or grant a global role {0} to an applicaton role

Action:
Do not add a global role to members of an application role and do not grant a global role to an application role.

JPS-20004
Principals can not contain global role.

Category:
Security

Cause:
Principals contain global role {0}

Action:
Remove global role from principals.

JPS-20005
Cannot delete global role "{0}".

Category:
Security

Cause:
Global role "{0}" is referenced in a Policy defined in an Application.

Action:
Make sure the global role is not referenced in any application policy,then remove it.

JPS-20006
Authorization policy is not supported in global policy.

Category:
Security

Cause:
Authorization policy is not supported in global policy.

Action:
Do not create authorization policies in global policy.

JPS-20007
Permission grant is not supported in global policy

Category:
Security

Cause:
Permission grant is not supported in global policy.

Action:
Do not grant permissions in global policy

JPS-20008
{0} : {1} in global policy which are referenced in application have been changed but not distributed

Category:
Security

Cause:
{0} : {1} in global policy which are referenced in application have been changed but not distributed.

Action:
Distribute global policy firstly

JPS-20010
Attribute name {0} already exist in {1}.

Category:
Programmatic

Cause:
Attribute name {0} already exist in {1}

Action:
Choose another name

JPS-20011
Function name {0} already exist in {1}.

Category:
Programmatic

Cause:
Function name {0} already exist in {1}

Action:
Choose another name

JPS-20012
Global attribute {0} is used in application {1}.

Category:
Programmatic

Cause:
Global attribute {0} is used in application policy {1}

Action:
Make sure the global attribute is not used in any applications including global policy

JPS-20013
Global function {0} is used in application {1}.

Category:
Programmatic

Cause:
Global function {0} is used in application policy {1}

Action:
Make sure the global function is not used in any applications including global policy

JPS-20014
Policy domain is not supported in global policy

Category:
Security

Cause:
Policy domain is not supported in global policy.

Action:
Do not use policy domain in global policy

JPS-20020
Resource type name {0} already exists in application {1}.

Category:
Programmatic

Cause:
Resource type name {0} already exists in application {1}

Action:
Choose another name

JPS-20021
Global resource type {0} is used in application {1}.

Category:
Programmatic

Cause:
Resource type {0} is used in application {1}

Action:
Make sure global resource type is not used in any application

JPS-20022
Global policy can not be unbound from SM

Category:
Programmatic

Cause:
Global policy can not be unbound from SM

Action:
Do not unbind global policy from SM

JPS-20050
Combining algorithm {0} not found.

Category:
Programmatic

Cause:
Combining algorithm not found.

Action:
Make sure the used combining algorithm exists.

JPS-20051
Exception in converting execution frequency {0}, message is {1}

Category:
Programmatic

Cause:
Exception in converting value of algorithm execution frequency.

Action:
Make sure the execution frequency is valid.

JPS-20052
Exception in converting algorithm usage {0}, message is {1}

Category:
Programmatic

Cause:
Exception in converting value of algorithm usage.

Action:
Make sure the usage is valid.

JPS-20053
A combining algorithm must be provided if policy is using more than one rule.

Category:
Programmatic

Cause:
Policy uses multiple rules, but no combining algorithm provided.

Action:
Provide a combining algorithm.

JPS-20054
A acl match type must be provided if policy is a RAS one.

Category:
Programmatic

Cause:
RAS policy has no acl match type to be provided.

Action:
Provide a ACL Match Type.

JPS-20055
A list of RAS policy rule must be provided if policy is a RAS one.

Category:
Programmatic

Cause:
RAS policy has no policy rule to be provided.

Action:
Provide policy rule(s).

JPS-20056
A list of RAS resource must be provided if policy is a RAS one.

Category:
Programmatic

Cause:
RAS policy has no resource to be provided.

Action:
Provide resource(s).

JPS-20060
Number of input parameters to the function and provided value types for them are not of same size.

Category:
Programmatic

Cause:
Number of input parameters to the function and provided value types for them are not of same size.

Action:
Parameter value types, if provided, must be provided for all input parameters

JPS-20061
Value collection added to expression is null.

Category:
Programmatic

Cause:
Value collection added to expression is null.

Action:
Provide a non-nulll collection of values to expression.

JPS-20062
Value collection passed to input parameter when a single object is expected.

Category:
Programmatic

Cause:
Value collection passed to input parameter when a single object is expected.

Action:
Provide a single object as input parameter.

JPS-20063
Wrong type of collection passed as input parameter; expected type is {0}, provided {1}.

Category:
Programmatic

Cause:
Wrong type of collection passed as input parameter; expected type is {0}, provided {1}.

Action:
Provide correct type of collection as function input parameter.

JPS-20064
Function {0} is unknown.

Category:
Programmatic

Cause:
Function {0} is unknown.

Action:
Provide correct function.

JPS-20070
In mixed mode, PDP configuration id could not be null

Category:
Programmatic

Cause:
PDP configuration id is missing.

Action:
Specify the PDP configuration id

JPS-20100
Rules {0} for policy {1} is in use by other policies. It will not be deleted.

Category:
Security

Cause:
Rule {0} of policy {1} is shared by other policies.

Action:
Provide correct Rule.

JPS-20101
Policy {0} is referred by one or more policy sets. It can not be deleted if cascading is set to false.

Category:
Security

Cause:
Policy {0} is referred by other policie sets.

Action:
Either use cascading delete or remove references from policy sets.

JPS-20102
Rule {0} used in policy is not sharable. The policy will not be created or updated.

Category:
Security

Cause:
Rule {0} used in policy is not sharable.

Action:
Provide correct Rule.

JPS-20103
Policy can not have both private rules and sharable rules.

Category:
Security

Cause:
Policy can not have both private rules and sharable rules.

Action:
Provide correct Rule.

JPS-20104
Exclusive rule {0} can not be deleted explicitly.

Category:
Security

Cause:
Exclusive rule {0} can not be deleted explicitly.

Action:
Delete the referred policy.

JPS-20105
The permission {0} has no target name.

Category:
Programmatic

Cause:
Permission has no target name.

Action:
Make sure the usage is valid.If not revoke the permission.

JPS-20200
Adding attributes to data security resource type {0} is not allowed.

Category:
Security

Cause:
Attributes present in Data Security Resource Type.

Action:
Remove Attributes present in Data Security Resource Type.

JPS-20201
Adding matcher class to data security resource type {0} is not allowed.

Category:
Security

Cause:
Matcher Class present in Data Security Resource Type.

Action:
Remove Matcher Class present in Data Security Resource Type.

JPS-20202
Hierarchical data security resource type {0} is not allowed.

Category:
Security

Cause:
Data Security Resource Type is Hierarchial.

Action:
Change Data Security Resource Type to Flat. It cannot be Hierarchial.

JPS-20203
Adding both actions and action collection references to data security resource type {0} is not allowed.

Category:
Security

Cause:
Both Actions and Action Collection References are added to Data Security Resource Type.

Action:
Add either Actions or Action Collection References to Data Security Resource Type.

JPS-20204
Adding null data security information object to data security resource type {0} is not allowed.

Category:
Security

Cause:
Null data security information object found for data security resource type.

Action:
Add data security information object to data security resource type.

JPS-20205
Data source name is required for a data security resource type {0}.

Category:
Security

Cause:
Data security information object found for data security resource type has no data source name.

Action:
Provide valid data source name for data security information object for data security resource type.

JPS-20206
Invalid value for data source type of data security resource type {0}.

Category:
Security

Cause:
Data security information object found for data security resource type has invalid data source type.

Action:
Data Security information object found for data security resource type has invalid data source type

JPS-20207
Constraint required for data security resource type {0} as data source type is virtual.

Category:
Security

Cause:
Virtual data source type requires data source constraint to be present.

Action:
Provide valid data source constraint for virtual data source.

JPS-20208
Actions List cannot contain actions that are inherited by default for resource type {0}.

Category:
Security

Cause:
Actions list in resource type contains default inherited data security actions.

Action:
Remove default data security actions from data security resource type.

JPS-20209
Duplicate column definition (same column names) not allowed in data source of resource type {0}.

Category:
Security

Cause:
Duplicate column definition (same names) in secured data source in resource type.

Action:
Remove duplicate column definition from secured data source.

JPS-20210
Action collection reference name {1} referred in resource type {0} not found in policy store.

Category:
Security

Cause:
Action collection reference in resource type not found in the policy store.

Action:
Either create action collection in store or remove the reference from resource type.

JPS-20220
Data Security Resource Type should be present for Data Security Resource {0}.

Category:
Security

Cause:
No RAS resource type present for RAS resource OR is not of type RAS resource type.

Action:
Add RAS resource type for RAS resource.

JPS-20221
For data security resource {0} SQL predicate or XML expression is required.

Category:
Security

Cause:
Both SQL predicate and XML expression missing in data security resource.

Action:
Add either SQL Predicate or XML expression to data security resource.

JPS-20240
Multiple rules not allowed for triton policy {0}.

Category:
Security

Cause:
Multiple rules in triton data security policy.

Action:
Add only one rule to triton data security policy.

JPS-20241
Data security policy {0} has invalid type {1} and category {2}.

Category:
Security

Cause:
Invalid policy category and type combination.

Action:
Provide valid policy category and type combination.

JPS-20242
RAS policy only takes resources with same resource type.

Category:
Security

Cause:
RAS Policy have resources with different resource types.

Action:
Provide resources just with same resource type for RAS policy.

JPS-20243
For RASParameterValue, only EXACT matcher is supported.

Category:
Security

Cause:
Search RAS Policy by RASParameterValue ONLY support MATCHER.EXACT.

Action:
Use MATCHER.EXACT for search by RASParameterValue.

JPS-20244
For RASParameterValue, only EQUALITY comparator is supported.

Category:
Security

Cause:
Search RAS Policy by RASParameterValue ONLY support COMPARATOR.EQUALITY.

Action:
Use COMPARATOR.EQUALITY for search by RASParameterValue.

JPS-20260
RAS Resource type name referred in RAS policy set {0} is Null.

Category:
Security

Cause:
RAS resource type reference in RAS policy set is Null.

Action:
Either create given resource type in store beforehand or use an existing one.

JPS-20261
Data security policy set {0} has invalid type {1} and category {2}.

Category:
Security

Cause:
Invalid policy set category and type combination.

Action:
Provide valid policy set category and type combination.

JPS-20262
Policy set {0} is an ACL protecting an Attribute Collection and cannot be deleted.

Category:
Security

Cause:
Attempt to delete ACL that is protecting an Attribute Collection.

Action:
Check that the ACL is not protecting any Attribute Collection.

JPS-20263
RAS Policy set only takes policies whose ras resources are of same ras resource type.

Category:
Security

Cause:
RAS policy set only takes policies whose ras resources are of same ras resource type.

Action:
Use ras policies with same ras resource type for ras policy set.

JPS-20264
The length of RAS {0} name plus the length of RAS application name can not exceed 29.

Category:
Security

Cause:
The length of RAS artifact name plus the length of ras application name exceeds 29.

Action:
Shorten the RAS artifact name

JPS-20265
The name of RAS {0} is allowed to consist of only alphanumeric characters and the special characters $, _, and #, and MUST begin with a letter.

Category:
Security

Cause:
The RAS artifact name is allowed to consist of only alphanumeric characters and the special characters $, _, and #, and MUST begin with a letter.

Action:
Change the RAS artifact name

JPS-20300
The action or implied action "{0}" already exists in action collection "{1}" or its parent(s).

Category:
Security

Cause:
Duplicate action or implied action found in action collection or one of its parents.

Action:
Verify the action and implied action lists of this action collection and its parents.

JPS-20301
The action collection "{0}" is already referenced in action collection "{1}" or its parent(s).

Category:
Security

Cause:
Duplicate action collection reference found in action collection or one of its parents.

Action:
Verify the action collection reference lists of this action collection and its parents.

JPS-20302
The action collection "{0}" already exists in application policy "{1}".

Category:
Security

Cause:
Action collection already exists in the application.

Action:
Verify the action collection in the application or try modify operation.

JPS-20303
The action collection "{0}" was not found in application policy "{1}".

Category:
Security

Cause:
Action collection not found in application.

Action:
Verify the action collection is present in the application.

JPS-20304
The action collection "{0}" is in use by another policy object.

Category:
Security

Cause:
Action collection is in use by another policy object.

Action:
Verify the usages of the action collection.

JPS-20305
Create, modify & delete operations are not permitted on built-in action collection "{0}".

Category:
Security

Cause:
The action collection being deleted, created or modified is built-in in the database.

Action:
Use a different name for the action collection.

JPS-20306
Action {0} referred in implied action {1} is not defined in action collection {2} or any of its parents.

Category:
Security

Cause:
The mapping specified for given implied action is not found in action collection or its parents.

Action:
Check the implied actions mappings.

JPS-20307
The action or implied action "{0}" already exists in implied action "{1}".

Category:
Security

Cause:
The mapping specified for given implied action contains duplicate actions.

Action:
Check the implied actions mappings.

JPS-20308
The implied action "{0}" refers to itself.

Category:
Security

Cause:
The mapping specified for given implied action contains reference to itself.

Action:
Check the implied actions mappings.

JPS-20320
"{0}" is not a RAS target database.

Category:
Security

Cause:
The SM is not a RAS target database.

Action:
make sure the name corresponds to a RAS target database

JPS-20321
"{0}" is not a RAS application.

Category:
Security

Cause:
The application is not a RAS application.

Action:
make sure the name corresponds to a RAS application

JPS-20322
"{0}" is not found or it is not a RAS target database.

Category:
Security

Cause:
RAS target database not found

Action:
make sure the name corresponds to a RAS target database

JPS-20350
All of handlerSchemaName, handlerPackageName and handlerFunctionName must be present or must be null in an attribute collection.

Category:
Security

Cause:
Atleast one of schema name, package name or function name of handler function is null.

Action:
Verify the schema name, package name and function name of handler function.

JPS-20351
The attribute "{0}" already exists in attribute collection "{1}".

Category:
Security

Cause:
Duplicate attribute found in attribute collection.

Action:
Verify the attribute list of this attribute collection and its parents.

JPS-20352
Attributes in attribute collection must be of category DYNAMIC.

Category:
Security

Cause:
Category of added attribute was wrong.

Action:
Verify the added attribute is of category DYNAMIC.

JPS-20353
The attribute collection "{0}" already exists in application policy "{1}".

Category:
Security

Cause:
Attribute collection already exists in the application.

Action:
Verify the attribute collection in the application or try modify operation.

JPS-20354
The attribute collection "{0}" was not found in application policy "{1}".

Category:
Security

Cause:
Attribute collection not found in application.

Action:
Verify the attribute collection is present in the application.

JPS-20355
Attributes in attribute collection must be single-valued.

Category:
Security

Cause:
Multi-valued attributes not supported.

Action:
Verify the added attribute(s) are all single-valued.

JPS-20356
The ACE(Policy Rule) "{0}" is not present in the application.

Category:
Security

Cause:
ACE(policy rule) protecting Attribute collection not found in application.

Action:
Verify the ACE(Policy Rule) is present in the application.

JPS-20357
The attributes in an attribute collection "{0}" is null or empty.

Category:
Security

Cause:
RASAttribute list is null or empty

Action:
Make sure RASAttribute list is not null or empty.

JPS-20400
The definition for attribute "{0}" exists in the application policy with wrong category. Expected: {1}, Found: {2}

Category:
Security

Cause:
Attribute definition exists in application with different category than expected.

Action:
Verify the attribute definition in the application.

JPS-20401
The definition for attribute "{0}" exists in the application policy with wrong type. Expected: {1}, Found: {2}

Category:
Security

Cause:
Attribute definition exists in application with different type than expected.

Action:
Verify the attribute definition in the application.

JPS-20403
Attribute designator functionality is not supported for this schema version.

Category:
Security

Cause:
Attribute designator functionality is not supported for this schema version.

Action:
Don't use designator functionality or upgrade to newer version.

JPS-20411
Invalid match function. Match function for a constraint must take two input parameters, provided function requires {0} input parameters.

Category:
Security

Cause:
Match function for constraint does not take 2 input parameters.

Action:
Provide a corret match function for constraint.

JPS-20412
Invalid match function. Both input parameters to a match function must be of same data type; provided function takes input parameters of type {0} and {1}.

Category:
Security

Cause:
Match function for constraint musts take two input parameters of same data type.

Action:
Provide a correct match function for constraint.

JPS-20413
Invalid match function. First parameter for a match function must be a single value.

Category:
Security

Cause:
Match function for a constraint cannot take bag or set of values.

Action:
Provide a correct match function for constraint.

JPS-20414
Mismatch of attribute category in constraint. Expected {0}, actual {1}.

Category:
Security

Cause:
Category of attribute provided to the constraint must either be dynamic or match the constraint type.

Action:
Provide attribute with correct category type to the constraint.

JPS-20415
The data type {0} of attribute "{1}" does not match data type {2} of function second parameter passed to AttributeValueAssertion.

Category:
Security

Cause:
Attribute data type and expected function parameter data type are different.

Action:
Verify the data type of attribute entry passed to AttributeValueAssertion.

JPS-20416
Data type of value and expected input parameter type of function provided for attribute value assertion does not match. Expected type {0}, provided {1}

Category:
Security

Cause:
Data type of value and expected input parameter type of function provided for attribute value assertion does not match.

Action:
Provide value with correct data type to the constraint.

JPS-20417
Constraints are only supported for TargetEntry and SimpleTargetEntry

Category:
Security

Cause:
Constraints are supported only for TargetEntry and SimpleTargetEntry.

Action:
If a constraint must be used, add it using a TargetEntry or SimpleTargetEntry.

JPS-20420
Function Element is not supported as return type of a function.

Category:
Security

Cause:
Function Element is not supported as return type of a function.

Action:
Provide some other return type.

JPS-20421
Data type for a Function Element input parameter must be OpssString.

Category:
Security

Cause:
Data type for a Function Element input parameter must be OpssString.

Action:
Provide correct data type.

JPS-20422
Function Element not supported for this version of policystore.

Category:
Security

Cause:
Function element not supported for this schema version.

Action:
Don't use function element or upgrade.

JPS-20423
AttributeAssignment can not be defined using a Function Element.

Category:
Security

Cause:
Attribute assignment cannot be defined using a function element.

Action:
Don't use function element.

JPS-20500
Quoted name for {0}, must be terminated by double-quote (").

Category:
Security

Cause:
Quoted id for triton entity needs to be terminated with double-quote(").

Action:
Verify the id provided.

JPS-20501
Length of {0} name must be between 1 and 30 characters (excluding the quotes ("), in case of quoted identifier), but was {1}

Category:
Security

Cause:
Id for triton entity has invalid length.

Action:
Verify the id provided.

JPS-20502
Quoted name for {0} contains invalid character "{1}" at position {2}. Quoted names must not contain null character(\0) or double-quote(") within the name

Category:
Security

Cause:
Quoted id for triton entity has invalid character.

Action:
Verify the id provided.

JPS-20503
Unquoted name for {0} contains invalid character "{1}" at position {2}. Unquoted names must begin with an alphabet. They may contain a letter, digit, underscore(_), dollar($), hash(#), or dot(.) symbols at other positions.

Category:
Security

Cause:
Unquoted id for triton entity has invalid character.

Action:
Verify the id provided.

JPS-20504
The name "{0}" is an implicit object name in the database and cannot be used as a name for {1}.

Category:
Security

Cause:
Id provided for triton entity is an implicit object name in the database.

Action:
Verify the id provided.

JPS-20505
The value "{0}" is of an unsupported type.

Category:
Security

Cause:
Parameter value is using an invalid type.

Action:
Verify the parameter value provided.

JPS-20521
A simple target must have at least one resource action entry or permission set reference.

Category:
Security

Cause:
A simple target must have at least one resource action entry or permission set reference.

Action:
Provide resource actions or permission sets.

JPS-20600
MetaData-Provisioned is true, but no meta data found in policy object {0}.

Category:
Programmatic

Cause:
MetaData-Provisioned is true, but no meta data found in policy object {0}.

Action:
Check the policy store, make sure it is in an consistent state.

JPS-20601
Provided version "{0}" is invalid. Only alphabetic characters, digits, underscores, and dots are allowed.

Category:
Programmatic

Cause:
Provided version {0} is invalid. Only alphabetic characters, digits, underscores, and dots are allowed.

Action:
Provide a valid version.

JPS-20602
Provided meta data {0} is invalid. Reason: {1}

Category:
Programmatic

Cause:
Provided meta data {0} is invalid. Reason: {1}.

Action:
Provide a valid meta data.

JPS-90600
Security Module with the configuration id {0} already exists.

Category:
Security

Cause:
Security Module with the configuration id {0} already exists.

Action:
Provide a unique configuration id.

JPS-90601
Failed to create Security Module with the configuration id {0}, with error {1}

Category:
Security

Cause:
Failed to create Security Module with the configuration id {0}, with error {1}

Action:
Check error message for further details.

JPS-90602
Security Module with the configuration id {0} not found.

Category:
Security

Cause:
Security Module with the configuration id {0} not found.

Action:
Make sure the configuration id is valid.

JPS-90603
AuditService is improperly configured.

Category:
Security

Cause:
Audit Service is not initializable.

Action:
Configure an audit server for audit trails

JPS-90604
Security Module with the configuration id {0} successfully created.

Category:
Security

Cause:
Security Module with the configuration id {0} successfully created.

Action:
Audit message, no action required

JPS-90605
Security Module with the configuration id {0} successfully modified.

Category:
Security

Cause:
Security Module with the configuration id {0} successfully modified.

Action:
Audit message, no action required

JPS-90606
Security Module with the configuration id {0} successfully deleted.

Category:
Security

Cause:
Security Module with the configuration id {0} successfully deleted.

Action:
Audit message, no action required

JPS-90607
Security Module with the configuration id {0} successfully retrieved.

Category:
Security

Cause:
Security Module with the configuration id {0} successfully retrieved.

Action:
Audit message, no action required

JPS-90608
Failed to modify Security Module with the configuration id {0}, with error {1}

Category:
Security

Cause:
Failed to modify PIP with the configuration id {0}, with error {1}

Action:
Check error message for further details.

JPS-90620
PIP with the configuration id {0} already exists.

Category:
Security

Cause:
PIP with the configuration id/name {0} already exists.

Action:
Provide a unique configuration id/name.

JPS-90621
Failed to create PIP with the configuration id {0}, with error {1}

Category:
Security

Cause:
Failed to create PIP with the configuration id {0}, with error {1}

Action:
Check error message for further details.

JPS-90622
PIP with the configuration id {0} not found.

Category:
Security

Cause:
PIP with the configuration id/name {0} not found.

Action:
Make sure the configuration id/name is valid.

JPS-90623
PIP with the configuration id {0} successfully created.

Category:
Security

Cause:
PIP with the configuration id {0} successfully created.

Action:
Audit message, no action required

JPS-90624
PIP with the configuration id {0} successfully modified.

Category:
Security

Cause:
PIP with the configuration id {0} successfully modified.

Action:
Audit message, no action required

JPS-90625
PIP with the configuration id {0} successfully deleted.

Category:
Security

Cause:
PIP with the configuration id {0} successfully deleted.

Action:
Audit message, no action required

JPS-90626
PIP with the configuration id {0} successfully retrieved.

Category:
Security

Cause:
PIP with the configuration id {0} successfully retrieved.

Action:
Audit message, no action required

JPS-90627
Failed to modify PIP with the configuration id {0}, with error {1}

Category:
Security

Cause:
Failed to modify PIP with the configuration id {0}, with error {1}

Action:
Check error message for further details.

JPS-90630
Application Policy with the configuration id {0} not found.

Category:
Security

Cause:
Application with the id {0} not found.

Action:
Make sure the Appplication Policy is valid.

JPS-90631
SM Binding with the configuration id {0} and application name {1} successfully retrieved.

Category:
Security

Cause:
SM Binding with the configuration id {0} and application name {1} successfully retrieved.

Action:
Audit message, no action required

JPS-90632
SM with the configuration id {0} to application bindings retrieved.

Category:
Security

Cause:
SM with the configuration id {0} to application bindings retrieved.

Action:
Audit message, no action required

JPS-90633
SM with the configuration id {0} and application name {1} successfully unbound.

Category:
Security

Cause:
SM with the configuration id {0} and application name {1} successfully unbound.

Action:
Audit message, no action required

JPS-90634
PIP Binding with the configuration id {0} and application name {1} successfully retrieved.

Category:
Security

Cause:
PIP Binding with the configuration id {0} and application name {1} successfully retrieved.

Action:
Audit message, no action required

JPS-90635
PIP with the configuration id {0} to application bindings retrieved.

Category:
Security

Cause:
PIP with the configuration id {0} to application bindings retrieved.

Action:
Audit message, no action required

JPS-90636
PIP with the configuration id {0} and application name {1} successfully unbound.

Category:
Security

Cause:
PIP with the configuration id {0} and application name {1} successfully unbound.

Action:
Audit message, no action required

JPS-90637
Failed to create SM binding with the configuration id {0}, with error {1}

Category:
Security

Cause:
Failed to create SM binding with the configuration id {0}, with error {1}

Action:
Check error message for further details.

JPS-90638
Failed to create PIP binding with the configuration id {0}, with error {1}

Category:
Security

Cause:
Failed to create PIP binding with the configuration id {0}, with error {1}

Action:
Check error message for further details.

JPS-90639
Application {0} already bound to configuration {1}

Category:
Security

Cause:
Application {0} already bound to configuration {1}

Action:
No need to bind again

JPS-90640
Failed to unbind SM configuration

Category:
Security

Cause:
Failed to unbind SM with the configuration id {0}, with error {1}

Action:
Check error message for further details.

JPS-90641
Failed to unbind PIP Configuration

Category:
Security

Cause:
Failed to unbind PIP with the configuration id {0}, with error {1}

Action:
Check error message for further details.

JPS-90642
The non-controlled policy distribution mode application {0} can not be bound to SM configuration

Category:
Security

Cause:
The non-controlled policy distribution mode application can not be bound to SM configuration

Action:
Bind controlled policy distribution mode application

18
MDS-00001 to MDS-92010

MDS-00001
exception in Metadata Services layer

Category:
Programmatic

Cause:
An exception occurred in the Metadata Services layer.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action.

MDS-00002
unexpected internal error

Category:
Programmatic

Cause:
An unexpected internal error occurred.

Action:
Contact Oracle Support Services.

MDS-00003
error connecting to the database

Category:
Configuration

Cause:
A database connection to the metadata repository could not be established.

Action:
Contact the database administrator or system administrator to get the problem resolved.

MDS-00005
unable to find XML element or text "{0}"

Category:
Programmatic

Cause:
The XML element with the given local name or the text node containing the given data could not be located by traversing through the document while applying customizations to a metadata object. The internal in-memory MDocument structure may be corrupted.

Action:
Retry the operation. Contact Oracle Support Services if the problem persists.

MDS-00008
Attribute "{0}" is not allowed for element {1} namespace {2} in metadata object {3}.

Category:
Programmatic

Cause:
An attempt was made to add an attribute to an element that does not conform to the element"s schema definition.

Action:
If the Bean API is being used, then determine if the beans need to be regenerated. Otherwise, inspect the element definition for valid attributes.

MDS-00010
DuplicateRefException. In document {0} there are multiple elements with the same ID {1}.

Category:
Programmatic

Cause:
Either an element was being added with an ID that already existed within the document, or a pre-existing document had multiple elements with the same ID.

Action:
Change the ID of the elements so that there is no ID duplication.

MDS-00011
unable to create configuration object or MDSInstance due to invalid configuration information: {0}

Category:
Configuration

Cause:
The MDS configuration was invalid.

Action:
Refer to the MDS specification and correct the configuration.

MDS-00012
invalid value "{0}" for attribute {1} (type = "{2}") in metadata object {3}

Category:
Data

Cause:
The value provided for the named attribute was invalid. For example, this error could occur if a named JNDI connection name is incorrect.

Action:
Provide a valid attribute value.

MDS-00013
no metadata found for metadata object "{0}"

Category:
Data

Cause:
MDS was unable to locate the given metadata object.

Action:
Confirm the name and location of the metadata object, its existence in the configured metadata stores, and that it is in an accessible namespace.

MDS-00015
Translation ignored in document "{0}": element with localRef "{1}" not found

Category:
Data

Cause:
A translation could not be applied because the underlying element to be translated was not found.

Action:
If the element is expected, check the base document and any customizations to locate it.

MDS-00016
Ignoring customization for instruction type "{0}" in metadata object "{1}" for customization layer "{2}"/"{3}": not finding element with local reference "{4}"

Category:
Data

Cause:
A customization was not applied because the underlying element to be customized was not found.

Action:
If the element is expected, examine the base document and any customizations to locate the element.

MDS-00017
Customization instruction generated for "{0}" uses local reference(s) : "{1}" which is not upgrade safe.

Category:
Data

Cause:
The customization instruction contained a local reference that was not deemed safe for an upgrade operation.

Action:
Ensure that the local reference used in the customization instruction would be safe during an upgrade operation.

MDS-00018
Fixed customization for instruction type "{0}" in metadata object "{1}" for customization layer "{2}"/"{3}": not able to find the referenced element with local reference "{4}", inserted the customized element at the best possible location.

Category:
Data

Cause:
A customization was fixed because the referenced element was not found.

Action:
Correct the customized element's position if needed.

MDS-00019
Customization document contains an invalid instruction "{0}".

Category:
Data

Cause:
A customization document that was being applied contained an unrecognized instruction.

Action:
Retry the operation. If necessary, either remove the customization document, or edit it to correct or remove the offending instruction.

MDS-00020
Layer value "{0}" contains an invalid character.

Category:
Data

Cause:
Using a layer value that has an invalid character.

Action:
Layer value should conform to MDS naming standards.

MDS-00029
Invalid namespace: The namespace "{0}" has not been registered with the MetadataManager.

Category:
Configuration

Cause:
An attempt was made to access a document in an unknown location or namespace.

Action:
Ensure that the namespace reported is registered in the MDS configuration.

MDS-00032
cannot parse the input file: {0}

Category:
Data

Cause:
An exception occurred while parsing the file.

Action:
Record the accompanying error and contact the developers of the application.

MDS-00033
cannot load the input file: {0}

Category:
Files

Cause:
An exception occurred while loading the file.

Action:
Record the accompanying error and contact the developers of the application.

MDS-00034
cannot write to the output file: {0}

Category:
Files

Cause:
An attempt to write to the output file failed.

Action:
Record the accompanying error and contact the developers of the application.

MDS-00035
cannot load the class: {0}.

Category:
Configuration

Cause:
The class file could not be loaded.

Action:
Ensure the class is available on the classpath so that it can be loaded by the application.

MDS-00036
cannot instantiate the class: {0}

Category:
Configuration

Cause:
An exception occurred while instantiating a class.

Action:
Record the accompanying error and contact the developers of the application.

MDS-00037
cannot access the class: {0}

Category:
Configuration

Cause:
An attempt was made to access an inaccessible class file.

Action:
Record any accompanying errors and contact the developers of the application.

MDS-00039
error while attempting to parse the document {0} using SAX.

Category:
Data

Cause:
A SAX parsing exception occurred while trying to parse a document.

Action:
Record the accompanying error and contact the developers of the application.

MDS-00040
There are no namespaces registered.

Category:
Configuration

Cause:
The operation attempted requires at least one registered namespace.

Action:
Correct the MDS configuration to include the required namespace schemas.

MDS-00041
invalid classpath entry "{0}"

Category:
Configuration

Cause:
An entry on the application's classpath did not exist or was invalid.

Action:
Correct the application's classpath to remove the invalid entry.

MDS-00042
Classpath "{0}" does not contain any valid directories or jar files.

Category:
Configuration

Cause:
The application's classpath contained no valid entries.

Action:
Correct the application's classpath.

MDS-00043
A name pattern mapping for path {0} already exists.

Category:
Configuration

Cause:
The MDS configuration had duplicate namespace mappings.

Action:
The MDS configuration must be corrected to remove the duplicate namespace mappings.

MDS-00044
Metadata for MetadataObject with name {0} already exists in the configured store.

Category:
Configuration

Cause:
An attempt was made to create a new Metadata Object. However an object with the same MDSReference already existed.

Action:
The name or location of one of the objects must be changed.

MDS-00047
Use the flushChanges method on the MDSSession to commit the changes.

Category:
Programmatic

Cause:
Commit was disabled in the PTransaction that was being used.

Action:
Use the flushChanges method on the MDSSession to commit the changes.

MDS-00054
The file to be loaded {0} does not exist.

Category:
Configuration

Cause:
An attempt was made to load a persistent document using a URL but the underlying document was not found in the store.

Action:
Check that the document name is correct and that the store is correctly configured.

MDS-00058
Invalid Metadata Path: Metadata Path cannot be null.

Category:
Configuration

Cause:
The path used to create a FileMetadataStore was empty. It must point to a directory.

Action:
Correct the metadata store definition in the application configuration to specify a metadata path.

MDS-00068
Element with local name = {0}, namespace = {1} is not expected under Parent Element = {2} in document location = {3}

Category:
Configuration

Cause:
While parsing a document, a request was made to locate a type definition whose usage is either not defined or is not expected for the parent element within the schema definition.

Action:
Check the xml source and any customizations to be applied and ensure that the element with the given namespace is defined and in the correct location as specified by the schema definition.

MDS-00084
Parameter {0} is invalid.

Category:
Programmatic

Cause:
The supplied parameter was not of the expected type.

Action:
Ensure the parameter is of the expected type.

MDS-00085
Parameter {0} is missing.

Category:
Programmatic

Cause:
The named parameter was not supplied.

Action:
Ensure that the named parameter is supplied. If transferring documents ensure a parameter file name is supplied.

MDS-00089
Parameter {0} must have a value.

Category:
Programmatic

Cause:
A required parameter was null.

Action:
Ensure that the indicated parameter is not null when the method is called.

MDS-00090
Error in JNDI lookup operation on MDSInstance name {0}, JNDI name {1}: object found {2} is an instance of class {3} classloader {4}, expected an instance of class {5} classloader {6}.

Category:
Programmatic

Cause:
An object of an unexpected type was found, and it was bound to the JNDI context as the MDSInstance.

Action:
Make sure no user-written code is binding anything to the same JNDI name. If the error occurs again try restarting the application. If the error still occurs, contact Oracle Support Services.

MDS-00091
Unable to customize {0}, empty or null value for tip customization layer {1}

Category:
Configuration

Cause:
The customization layer configured as the tip, has a null or empty value.

Action:
Ensure that a valid value is supplied for the tip customization layer.

MDS-00092
DuplicateNodeException. The same bean instance {0} already exists in document {1}.

Category:
Programmatic

Cause:
An element was being added that already exists as the same bean instance within the document.

Action:
Either create a new bean instance or remove the duplicate before attempting to insert in the document.

MDS-00093
List of values provided for customization layer {0} was empty or null.

Category:
Programmatic

Cause:
The list of customization layer values was either empty or null.

Action:
Ensure that a valid list of layer values for the customization layer is provided.

MDS-00094
List of CustLayerUsage objects provided was empty or null.

Category:
Programmatic

Cause:
The list of CustLayerUsage objects was either empty or null.

Action:
Ensure that a valid list of CustLayerUsage objects is provided.

MDS-00095
The support to transfer customization documents based on the CustConfig and excluding customization documents of specific customization layers is not yet available.

Category:
Programmatic

Cause:
CustOption is created to transfer customization documents based on the CustConfig and to exclude customization documents of specific customization layers which is not yet supported in MDS Transfer.

Action:
Ensure CustOption is not created to use CustConfig and to exclude customization documents of specific customization layers.

MDS-00111
The value of the property {0} for the component {1} must be set to the default value.

Category:
Data

Cause:
The indicated component property did not have a default value.

Action:
Ensure the component property is given a default value.

MDS-00153
invalid value for indicator

Category:
Data

Cause:
The production of merged XML failed.

Action:
Verify the validity of XML documents and any schemas. If necessary forward these on to Oracle Support Services with the exception message and stack trace.

MDS-00154
The ContentHandler {0} does not implement org.xml.sax.ext.LexicalHandler.

Category:
Programmatic

Cause:
MergedXML was passed a ContentHandler that does not implement org.xml.sax.ext.LexicalHandler.

Action:
Use a ContentHandler that implements org.xml.sax.ext.LexicalHandler.

MDS-00155
unable to create a JSP file for document {0}

Category:
Files

Cause:
Oracle MDS was unable to create a JSP source document.

Action:
Examine the MDS base document, as well as any customizations and translations. If necessary, forward these to Oracle Support Services.

MDS-00156
unable to create a JSP output directory {0}

Category:
Files

Cause:
MDS-JSP integration failed because a problem was encountered while creating a directory.

Action:
Verify that you have permission to create this directory.

MDS-00157
unable to write to JSP file {0}

Category:
Files

Cause:
MDS-JSP integration failed because a problem was encountered while trying to write to a file.

Action:
Verify that you have permission to create this file.

MDS-00158
invalid directory: {0}

Category:
Files

Cause:
MDS-JSP integration failed. An attempt was made to write to an invalid directory.

Action:
Verify the value of the invalid directory.

MDS-00159
Invalid value "{0}" for {1} attribute (type = "{2}") in document {3}.

Category:
Programmatic

Cause:
An attempt was made to read or write an invalid attribute value.

Action:
Double-check the value and attribute type.

MDS-00160
no local name has been specified for a resource

Category:
Programmatic

Cause:
An attempt was made to create a resource without giving it a name.

Action:
Verify that the resource that was created is given a local name.

MDS-00161
no local name has been specified

Category:
Programmatic

Cause:
An attempt was made to create a resource without giving it a local name.

Action:
Verify that the resource that was created is given a local name.

MDS-00162
invalid attribute value

Category:
Programmatic

Cause:
An attempt was made to give to an invalid value to an attribute.

Action:
Verify that the attribute has a valid value.

MDS-00163
property value missing from element

Category:
Programmatic

Cause:
An element was missing a property value.

Action:
Ensure that each parameter used to create the element has a property value.

MDS-00164
There is a concurrent "{1}" operation on the document "{0}".

Category:
Data

Cause:
The document on which modification was being attempted had been updated by another user after it was retrieved.

Action:
Retrieve the document again.

MDS-00165
metadata Object "{0}" has changed

Category:
Data

Cause:
The creation, updating, or renaming of a metadata object failed due to conflicting changes made by another user.

Action:
Retrieve the document containing the metadata object again.

MDS-00166
unable to locate the unique identifier, {0}:{1}, that has been configured for the element {2}

Category:
Programmatic

Cause:
The element that required a unique identifier was created without one.

Action:
Add a unique identifier attribute to the element.

MDS-00167
Invalid local name for mapping "{0}" - an empty string is not allowed.

Category:
Programmatic

Cause:
A local name was given a null or empty value.

Action:
Supply a valid local name.

MDS-00168
MDS object {0} is being used after it or its MDSInstance or PManager has been released.

Category:
Session

Cause:
An MDS object was used after it or its MDSInstance or PManager had been released

Action:
Create a new MDSInstance and re-create the MDS object.

MDS-00169
The MDS instance is not ready for use because metadata deployment is in progress (status is "{0}"). Deployment messages so far are: "{1}".

Category:
Programmatic

Cause:
The MDS instance cannot be used until metadata deployment has finished.

Action:
Try again later after metadata deployment has completed.

MDS-00170
The MDS instance is not usable because metadata deployment failed with status "{0}".

Category:
Configuration

Cause:
Metadata deployment failed with the given status.

Action:
Please fix the error and redeploy the application's metadata using the importMAR operation on MDS Application Runtime MBean. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00171
Document "{0}" already has unsaved updates on another instance of this metadata object in this session.

Category:
Data

Cause:
An attempt was made to update metadata using more than one instance of the same metadata object at the same time in the same session.

Action:
Save the changes on the metadata object that already has updates before attempting to update it via another metadata object, or make further modifications on the metadata object on which updates have already been made.

MDS-00172
The value "{0}" of local unique attribute {1} on the {2} element that is being inserted or updated in document {3}, is already used by a sibling element.

Category:
Data

Cause:
An attempt was made to have two local unique attributes with the same value on elements that share the same parent.

Action:
Use a different value for the local unique attribute on the element that is being inserted or updated.

MDS-00173
Attribute {0} of element {1} in document {2} has a null value.

Category:
Data

Cause:
The value of the named attribute was null.

Action:
Provide a non-null value for the attribute or remove the attribute.

MDS-00174
A tenant scoped MDSInstance {0} is being requested with a null TenantId.

Category:
Session

Cause:
A tenant scoped MDSInstance was requested passing null for TenantId.

Action:
Supply a non null TenantId or request an unscoped MDSInstance.

MDS-00176
The operation on MDSInstance {0} cannot be performed as it is not tenant scoped.

Category:
Session

Cause:
The operation performed on the MDSInstance was invalid with a TenantId because it was not a tenant scoped MDSInstance.

Action:
Perform the operation on an MDSInstance initialized for multitenant operation.

MDS-00177
The operation on resource {0} cannot be performed as it is not configured to be owned by the current tenant scope.

Category:
Session

Cause:
The operation performed was illegal as the resource being created, updated or deleted has global scope and the current scope is tenant or the resource has tenant scope and the current tenant is global.

Action:
Check that the configuration of the namespaces and CustomizationClasses is correct and that the correct customization class list is being used.

MDS-00178
Multitenant MDSInstance {0} cannot be returned as a non-multitenant MDSInstance was requested with the current persistence configuration.

Category:
Session

Cause:
The configuration at the time the MDSInstance was requested did not match with the configuration when it was originally created.

Action:
Request an MDSInstance appropriate to the configuration.

MDS-00179
The requested MDSInstance {0} cannot be returned for TenantId {1} as it was originally created with multitenant enabled = {2}.

Category:
Session

Cause:
The configuration at the time the MDSInstance was requested did not match with the configuration when it was originally created.

Action:
Request an MDSInstance appropriate to the original configuration.

MDS-00180
Only a single tenant cache configuration is allowed.

Category:
Session

Cause:
The number of TenantCacheConfigs was not 1.

Action:
Pass a single tenant cache configuration object. Although the constructor for the TenantCacheConfigs class takes an array this is reserved for future use.

MDS-00181
Only a single tenant document cache configuration is allowed.

Category:
Session

Cause:
The number of TenantDocumentCacheConfigs was not 1.

Action:
Pass a single tenant document cache configuration object. Although the constructor for the TenantDocumentCacheConfigs class takes an array this is reserved for future use.

MDS-00182
Tenant cache configuration information cannot be requested for the global tenant.

Category:
Session

Cause:
Tenant cache configuration information was being requested for the global tenant.

Action:
Do not request the tenant cache configuration for the global tenant - use getCacheConfig directly from MDSConfig

MDS-00183
Tenant document cache configuration information cannot be requested for the global tenant.

Category:
Session

Cause:
Multitenant document cache information was being requested for the global tenant.

Action:
Do not request the tenant document cache configuration for the global tenant - use getDocumentCacheConfig from NamespaceConfig

MDS-00184
The relationship from {0} to {1} is invalid because the latter is configured as a global resource and cannot be referenced from a tenant resource because the corresponding relationship is defined with cascade delete enabled.

Category:
Session

Cause:
Relationships with cascade delete enabled were spanning tenant boundaries.

Action:
Reconfigure the relationship with cascade delete disabled or ensure the parent reference is within the same tenant scope.

MDS-00185
The relationship from {0} to {1} is invalid because the latter is configured as a global resource and cannot be referenced from a tenant resource because the corresponding relationship is defined with enforced integrity.

Category:
Session

Cause:
Relationships with defined referential integrity were spanning tenant boundaries.

Action:
Reconfigure the relationship without referential integrity or ensure the parent reference is within the same tenant scope.

MDS-00186
A {0} element is already present in the parent {1} element in document {2}, but with the QNameLUID identification mechanism only one is allowed.

Category:
Data

Cause:
An attempt was made to have two or more elements with same QName under same parent while QNameLUID identification mechanism is used.

Action:
Remove duplicate instances of elements with same QName

MDS-00187
The existing {0} element in the parent {1} element in document {2} is automatically removed, and new customized {0} element of "{3}"/"{4}" customization layer is inserted since with the QNameLUID identification mechanism, only one is allowed.

Category:
Data

Cause:
An attempt was made to have two or more elements with same QName under same parent while QNameLUID identification mechanism is used.

Action:
Removed duplicate instances of elements with same QName

MDS-00188
The relationship from {0} to {1} is invalid because the latter is configured as a tenant resource and cannot be referenced from a global resource.

Category:
Session

Cause:
An attempt was made to reference a tenant resource from a global resource.

Action:
Ensure all references from global resources are also global.

MDS-00189
The existing {0} element with unique id {1} in the parent {2} element in document {3} is automatically removed, and new customized {0} element with unique id {1} of "{4}"/"{5}" customization layer is inserted since {0} element is type-annotated to overwrite duplicates.

Category:
Data

Cause:
An attempt was made to have two or more elements with same QName under same parent having the same unique ID value while overwriteDuplicate mechanism is used.

Action:
Removed duplicate instances of elements with same QName having the same unique ID value

MDS-00190
A call to {0} on the current MDSSession does not specify the correct transaction key

Category:
Session

Cause:
The current MDS Session was created using a transaction key and the subsequent operation was either being attempted passing no key or a different one from that originally used.

Action:
If the MDS Session is created using a transaction key, then use the MDSSession API's that take a transaction key and use the same key.

MDS-00191
An exception occurred in PChangeListener {0}

Category:
Session

Cause:
The MetadataStoreCommunicator was attempting to notify the listener when an exception occurred.

Action:
Check the HandlePChanges method of the listener.

MDS-00192
Validation of {0} caused a NullPointerException: check there is an MDS bean object set on the MDS bean MO

Category:
Data

Cause:
This error most typically occurs when a Bean MO has been created but no bean object has been set on it.

Action:
Check that an MDS bean is set on this MO. Failing that, examine the stack for clues for alternative causes.

MDS-00193
Document with the MDSReference {0} contains an ID attribute with an invalid value: {1}

Category:
Data

Cause:
The value of the ID attribute is invalid according to the schema definition.

Action:
Ensure that the ID conforms to the schema definition .

MDS-00194
Auditing is disabled for component {0}.

Category:
Configuration

Cause:
There was an error registering the audit event definition(s) for the component.

Action:
Ensure that the audit event definitions for the component are valid and that the audit service is functional.

MDS-00195
The custom audit event of type "{0}" that was associated with "{1}" is not audited because the MDS object was unmodified since the last time the changes in the MDSSession were committed.

Category:
Programmatic

Cause:
MDS object associated with the event was unmodified since the last time the changes in the MDSSession were committed. A custom audit event is discarded if the associated MDSObject is not modified.

Action:
No action required.

MDS-00196
The MDSSession referenced by the audit component "{0}" is invalid.

Category:
Programmatic

Cause:
The MDS audit support instance is being used even after the MDSSession that was used to created it is no longer referenced.

Action:
Fetch the audit support instance from the MDSSession and retry the operation.

MDS-00197
An internal error occurred when processing MetadataObject {0} with document {1}.

Category:
Session

Cause:
An error occurred in the LayeredCache processing.

Action:
Check for log messages. If the problem persists, clear the MDS cache and contact Oracle Support Services.

MDS-00198
The requested object is deleted in the current PTransaction

Category:
Data

Cause:
The requested document was deleted in an earlier part of the PTransaction and not replaced.

Action:
Review whether the document needed to be deleted or replace with a new version.

MDS-00199
The requested object is deleted in the current MDSSession

Category:
Data

Cause:
The requested document was deleted in an earlier part of the MDSSession and not replaced.

Action:
Review whether the document needed to be deleted or replace with a new version.

MDS-00200
Reference not found in Document

Category:
Data

Cause:
Unable to locate the reference within the named Metadata Object.

Action:
Check that the reference is correct.

MDS-00201
PDocument not found in MetadataStore : {0}

Category:
Data

Cause:
The requested persistence document was not found in the given MetadataStore.

Action:
Check that the requested name is correct and that the store is mapped to the namespace correctly .

MDS-00202
The Document was not found on the classpath

Category:
Data

Cause:
The requested document was not found on the classpath.

Action:
Check that the document is available on the classpath as a resource .

MDS-00203
An error occurred while attempting to process Element "{0}" from customization document {1} because the change conflicts with information in the base document or changes made by a prior customization

Category:
Data

Cause:
An error occurred during parsing of a customization - see cause.

Action:
Check for any conflicts between the customization and recent changes to the base document or other customizations being applied.

MDS-00204
Remove customization fails on element with local reference "{0}" in document "{1}"

Category:
Programmatic

Cause:
An attempt to remove a customization from an element has failed.

Action:
Reproduce the customization document without the desired customization.

MDS-00205
Unexpected error in ChangeEventParseEngine

Category:
Programmatic

Cause:
An error in the ChangeEventParseEngine.

Action:
Check for log messages. If the problem persists, contact Oracle Support Services.

MDS-00206
Unexpected error while collecting ElementTipCustInfo for a customized element

Category:
Programmatic

Cause:
An error occurred while gathering ElementTipCustInfo for a customized element.

Action:
Check for log messages. If the problem persists, contact Oracle Support Services.

MDS-00207
Cached Object {0} was removed from the MDS cache by thread {1} while being read. Retrying the read.

Category:
Session

Cause:
An object being accessed by MDS was removed from the cache before it could be used to return the requested data.

Action:
The notification can occur if there are concurrent updates to objects cached by MDS. If the notification persists review the MDS cache configuration.

MDS-00208
Root node deleted but not replaced.

Category:
Programmatic

Cause:
The root node of an XML document was deleted, but no replacement node was inserted.

Action:
Insert a replacement root node after deleting the root node.

MDS-00209
Exception adding logging data: " {0}".

Category:
Programmatic

Cause:
An exception was raised in the MDS diagnostic log processing.

Action:
Examine logs for the full exception stack and underlying cause.

MDS-00210
The TenantId supplied {0} does not match the current tenant context: {1}.

Category:
Session

Cause:
A TenantId was supplied to MDS that does not match the TenantId provided by the context.

Action:
Remove the TenantId from the deprecated API or correct the TenantId supplied.

MDS-00211
Action is not allowed on a tenant-specific MetadataStoreCommunicator.

Category:
Programmatic

Cause:
An attempt was made to invoke a method that is not allowed on a non-global tenant

Action:
This change has to be made in a global tenant context.

MDS-00212
Unable to execute a task in the DOMAIN partition in application {0} because the application in the DOMAIN partition is not currently in RUNNING state, or this is a Java SE application that has not initialized MDS in the DOMAIN context.

Category:
Session

Cause:
A task runner was required but unable to be found.

Action:
Ensure that the MDS application lifecycle listener is configured, or that MDS is initialized in the global tenant context before running in any other tenant context.

MDS-00213
It was not possible to lock the cached RootNode with root key {0}.

Category:
Session

Cause:
An error occurred in the LayeredCache processing due to cache contention on a specific object.

Action:
Check for log messages. If the problem persists, clear the MDS cache and contact Oracle Support Services.

MDS-00214
Error encountered while processing root node replacement customization instruction in tip customization layer document.

Category:
Programmatic

Cause:
The customization instructions in tip customization document might be corrupted.

Action:
Check for log messages. If the problem persists, contact Oracle Support Services.

MDS-00215
TenantId is not supported. Please use equivalent ServiceId api.

Category:
Programmatic

Cause:
An attempt was made to invoke MDS deprecated APIs with TenantId.

Action:
Replace TenantId based API with ServiceId based API.

MDS-00216
Notification Manager for MDSInstance {0} was unable to get an application scoped executor for dispatching events in the application context - using a global executor instead.

Category:
Session

Cause:
An attempt was made to get an application scoped executor outside of an application.

Action:
Check if the request should be running within the scope of an application.

MDS-00217
Notification Manager for MDSInstance {0} was unable to get an application scoped contextual proxy for dispatching global events in the tenant context - using a global contextual proxy instead.

Category:
Session

Cause:
An attempt was made to get an application scoped contextual proxy outside of an application.

Action:
Check if the request should be running within the scope of an application.

MDS-00218
Cannot create ServiceId with null Service UUID.

Category:
Configuration

Cause:
An attempt was made to create an MDS ServiceId with a null value.

Action:
Check lifecycle-config.xml and ensure that each 'service' element contains an 'id' attribute defined with a UUID value.

MDS-00219
Invalid resource passed to MDSFaceletsHelper: {0}.

Category:
Programmatic

Cause:
An invalid resource was passed to MDSFaceletsHelper.

Action:
Check exception message. Consider enabling oracle.mds.jrf logging for additional diagnostics.

MDS-00220
Document {0} to be loaded does not exist for label {1}.

Category:
Configuration

Cause:
An attempt was made to load a persistent document using a URL but the underlying document was not found in the DB MetadataStore.

Action:
Check that the document name is correct and that the DB MetadataStore and Label are correctly configured.

MDS-00221
Specified label {0} does not exist in {1} store.

Category:
Configuration

Cause:
The specified label did not exist in the metadata store.

Action:
Verify that the label name is correct and that the label exists in the metadata store, and then retry the operation.

MDS-00222
Invalid value "{0}" for {1} attribute (type = "{2}").

Category:
Programmatic

Cause:
An attempt was made to read or write an invalid attribute value.

Action:
Double-check the value and attribute type.

MDS-00223
Unable to retrieve pinned Customization Class value from Unified Sandbox For CustomizationClass : {0} with Name {1}.

Category:
Runtime

Cause:
An attempt was made to read a customization value with AutoMergeOverrideValue.PINNED, but no value was retreived from the Unified Sandbox.

Action:
Ensure Unified Sandbox is able to return a pinned value for this Customization Class.

MDS-00224
Customization of {0} Location: {1} is not permitted due to a package level restriction in the cust-restriction-library-config element of the mds-library-config.xml at jar/zip level.

Category:
Runtime

Cause:
A jar level restriction on customization has been specified for objects in this package in the cust-restriction-library-config element of the mds-library-config.xml file.

Action:
Check if customization of this object should be allowed and correct the entries in cust-restriction-library-config at the jar/zip level.

MDS-00225
Updating immutable StreamedObject "{0}" is not allowed.

Category:
Programmatic

Cause:
The StreamedObject being updated was immutable.

Action:
Ensure that the StreamedObject to be updated is mutable.

MDS-00226
Unable to determine the MDSContext while processing cached MDS content : {0}

Category:
Runtime

Cause:
An attempt was made to access an MDSContext but an MDSContext is not presently available to this thread.

Action:
Check for logged diagnostic messages, clear the MDS cache and if the problem persists contact Oracle Support Services.

MDS-00227
Failure in MDS Java Flight Recorder integration processing.

Category:
Configuration

Cause:
A failure occurred in MDS JFR integration processing.

Action:
Examine the exception for clues. Check the JVM FlightRecorder options.

MDS-00228
No MOParseListener instance provided to MOParseListenersBuilder to build MOParseListeners instance.

Category:
Programmatic

Cause:
An attempt was made to build MOParseListeners instance using MOParseListenersBuilder without providing any instances of MOParseListener.

Action:
Provide at least one instance of MOParseListener before building MOParseListeners instance using MOParseListenersBuilder.

MDS-00229
DuplicateRefException occurred while attempting to process prior customization layer.

Category:
Data

Cause:
There exists two or more elements with same id value in base document and/or prior customization layers.

Action:
Fix elements with duplicate id value in prior customization layers before processing tip customization layer.

MDS-00230
Unexpected metadata object parse error.

Category:
Programmatic

Cause:
An unexpected metadata object parse error occurred.

Action:
Check DupIdInsertResolver instance usage.

MDS-00231
ReplaceProcessingOption NOT a valid available ProcessingOption.

Category:
Data

Cause:
An attempt was made to use DupIdElementsFilter.REPLACE_PO to fetch collection of DupIdElementInfo instances while ReplaceProcessingOption is NOT a valid available ProcessingOption.

Action:
Ensure to use DupIdElementsFilter associated to valid available ProcessingOption.

MDS-00232
Selected resolution is NOT amongst one of the available ProcessingOptions.

Category:
Data

Cause:
An attempt was made to use a resolution which is NOT amongst one of the available ProcessingOptions.

Action:
Ensure to use resolution which is amongst one of the available ProcessingOptions.

MDS-00233
Selected resolution is NOT amongst one of the available CustApplyOptions.

Category:
Data

Cause:
An attempt was made to use a resolution which is NOT amongst one of the available CustApplyOptions.

Action:
Ensure to use resolution which is amongst one of the available CustApplyOptions.

MDS-00234
RestrictedSession in CustClassContext should not be null

Category:
Data

Cause:
An attempt was made to create an instance of CustClassContext without specifying a value for RestrictedSession.

Action:
Ensure a non null value is provided to CustClassContext.Builder.withRestrictedSession.

MDS-00235
MOReference {0} and MetadataObject {1} are not consistent.

Category:
Data

Cause:
An attempt was made to create a CustClassContext with both a MetadataObject and an MOReference which did not relate to the same MetadataObject.

Action:
Ensure that MetadataObject and MOReference are consistent.

MDS-00236
Customization of {0} is not allowed because it is not explicitly allowed by any extended metadata entry, file type or package restriction.

Category:
Configuration

Cause:
An attempt was made to customize a StreamedObject that was not customizable.

Action:
If the attempted customization is valid, the customization restrictions need to be modified to provide this ability. The customization restrictions can be defined in: An extended metadata file, the FileTypeConfig or MDSLibraryConfig. Also check the customization policy for the MDS session in use and the customization configuration.

MDS-00237
Timed out trying to obtain a lock on the cache.

Category:
Session

Cause:
It was not possible to obtain a lock on a WeakCache after waiting 30 seconds.

Action:
Consider using a diagnostic tool such as jconsole to identify the thread that is not relinquishing this lock.

MDS-00238
Document {0} is not configured as a customizable StreamedObject.

Category:
Configuration

Cause:
The Streamed Object requested has not been configured for customization.

Action:
Ensure customization-type attribute in cust-config is set to FULL_REPLACE and that the content-type is BINARY_STREAM.

MDS-00239
Layer-specific retrieval on immutable StreamedObject "{0}" is not allowed.

Category:
Programmatic

Cause:
The StreamedObject on which a LSOLayerRetrieval method was called is immutable.

Action:
Ensure that the StreamedObject is mutable before calling LSOLayerRetrieval methods.

MDS-00240
A rest request to update a resource requires If-Match.

Category:
Session

Cause:
A rest request to update a resource was issued without specifying an ETag in the If-Match Header.

Action:
Reissue the request with a valid If-Match Content header.

MDS-00241
A rest request to update a resource specified an out of date ETag.

Category:
Session

Cause:
A rest request to update a resource specified an out of date ETag in the If-Match content Header, possibly due to the resource having been updated by another session.

Action:
Re-request the resource to obtain an up to date Etag and reissue the update.

MDS-00242
A rest request to update a resource occurred outside a unified sandbox.

Category:
Session

Cause:
The MDSSession obtained from the ADFContext was not running within a unified sandbox.

Action:
Session options on the ADFContext should use a unified sandbox.

MDS-00243
The document {0} is not within the current unified sandbox.

Category:
Session

Cause:
The document's namespace is not configured to be contained within the active unified sandbox.

Action:
Verify that the document should be updateable and amend the unified sandbox configuration accordingly.

MDS-00244
There is no current ADFContext.

Category:
Session

Cause:
The operation requires that an ADFContext be present on the current thread.

Action:
Verify that the ADFContext is configured correctly.

MDS-00245
A Customization already exists for {0} for the current layer

Category:
Session

Cause:
An attempt was made to create a new customization when one already exists.

Action:
GET the existing customization and modify via PUT.

MDS-00246
A Customization does not exist for {0} for the current layer

Category:
Session

Cause:
An attempt was made to get an existing custimization which does not exist.

Action:
Check the naming of your resource and retry the operation.

MDS-00247
No tip customization layer defined while retrieving details for {0}

Category:
Session

Cause:
Customization Layers have not been defined on the current MDSSession.

Action:
Check the customization config for your environment.

MDS-00248
No support to object-merge VBCS base document.

Category:
Data

Cause:
VBCS base document requires object-merge.

Action:
Remove conflicting VBCS base document available in sandbox and retry sandbox refresh operation.

MDS-00249
No support to object-merge VBCS base document and/or its associated non-tip layer extensions.

Category:
Data

Cause:
VBCS base document or its associated non-tip layer extensions requires object-merge.

Action:
Remove conflicting VBCS base document and/or its associated non-tip layer extensions available in sandbox and retry sandbox refresh operation.

MDS-00500
No metadata store is configured to save the document {0}.

Category:
Configuration

Cause:
An attempt was made to save a document, when no writable store was configured.

Action:
Provide a writable metadata store to save the document.

MDS-00501
Document {0} cannot be deleted because no metadata store is configured.

Category:
Configuration

Cause:
An attempt to delete a document failed because there was no writable store configured.

Action:
To delete the document, provide a writable metadata store.

MDS-00503
The metadata path "{0}" does not contain any valid directories.

Category:
Data

Cause:
Either the metadata path was empty or directories on the metadata path did not exist.

Action:
Ensure that the metadata path is not empty and that the directories on the metadata path exist.

MDS-00504
failure to create document {0} because metadata store "{1}" is read-only

Category:
Data

Cause:
An attempt to create a document on a read-only metadata store failed.

Action:
To create the document, provide a writable metadata store.

MDS-00505
failure to save document {0} because metadata store "{1}" is read-only

Category:
Data

Cause:
An attempt to save a document to a read-only metadata store failed.

Action:
To save the document, provide a writable metadata store.

MDS-00506
failure to get child resources of package {0} because package does not exist in metadata store

Category:
Data

Cause:
Child resources for the package were not found because specified package did not exist in the metadata store.

Action:
Verify that the package exists in the metadata store, and then retry the operation.

MDS-00507
failure to delete document {0} because metadata store "{1}" is read-only

Category:
Data

Cause:
An attempt to delete a document from a read-only metadata store failed.

Action:
To delete the document, provide a writable metadata store and retry the operation.

MDS-00508
There is no content to be read for {0}.

Category:
Data

Cause:
An attempt was made to read empty metadata.

Action:
Verify that the metadata has valid content, and then retry the operation.

MDS-00509
failure to delete document {0} with file {1}

Category:
Data

Cause:
An error occurred while the document was being deleted.

Action:
Verify that the document exists and then retry the operation, or provide a document that exists in the store.

MDS-00510
failure to read document {0} because it is not found in the metadata path "{1}"

Category:
Data

Cause:
The document to be read was not found.

Action:
Verify that the metadata path is correct and that the document exists in the metadata path.

MDS-00511
failure to create document {0} at file {1}

Category:
Files

Cause:
An error occurred while creating the document in the file store.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00512
failure to create document {0} because file {1} already exists

Category:
Files

Cause:
An attempt was made to create a file that already existed in the metadata store.

Action:
Provide a different name for the file to be created, or delete the existing file first, and then retry the operation.

MDS-00513
failure to create package {0} because directory {1} already exists

Category:
Files

Cause:
An attempt to create a package failed because a directory by the same name already existed.

Action:
Provide a different name for the package to be created and retry the operation.

MDS-00514
failure to save document {0} to file {1}

Category:
Files

Cause:
An error occurred while saving the document to a file.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00515
failure to create document {0} in the metadata repository

Category:
Data

Cause:
An error occurred while the document was being created in the metadata repository.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00516
failure to create document {0} because it already exists in the metadata repository

Category:
Data

Cause:
An error occurred while the document was being created in the metadata repository because the document already existed.

Action:
Provide a different name or delete the existing document first, and then retry the operation.

MDS-00517
failure to create package {0} because it already exists in the metadata repository

Category:
Data

Cause:
An error occurred while the package was being created in the metadata repository because the package already existed.

Action:
Provide a different package name or delete the existing package first, and then retry the operation.

MDS-00518
failure to create package {0} in the metadata repository

Category:
Data

Cause:
An error occurred while the package was being created in the metadata repository.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00519
failure to delete document {0} from the metadata repository

Category:
Data

Cause:
An error occurred while the document was being deleted from the metadata repository.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00520
failure to read document {0} because it is not in the metadata repository

Category:
Data

Cause:
The document was not read because it did not exist in the metadata repository.

Action:
Verify that the document name is correct and that it exists in the metadata repository, and then retry the operation.

MDS-00521
error while reading document {0} from metadata repository

Category:
Data

Cause:
An error occurred while the document was being read from the metadata repository.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00522
failure to save document {0} to the metadata repository

Category:
Data

Cause:
An error occurred while the document was being saved to the metadata repository.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00526
failure to generate SAX parsing events for document {0}

Category:
Programmatic

Cause:
An error occurred while parsing the XML document.

Action:
Verify that the XML document is well-formed. Refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00531
failure to write to "{0}" because output to "{1}:" protocol is not supported

Category:
Programmatic

Cause:
An attempt to write modified metadata to a URL failed because the protocol is not supported.

Action:
Retry writing modified metadata to a supported protocol.

MDS-00533
Exception: {3} Attribute "{0}" with an invalid MDS reference "{1}" in document "{2}" is not stored as a typed dependency in the database repository.

Category:
Data

Cause:
An error occurred while adding a typed dependency from the specified attribute.

Action:
Refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00534
Exception: {3} Sub-object {0} in document {2} has invalid value "{1}" for unique identifier; typed dependencies from this sub-object are not stored in the database repository.

Category:
Programmatic

Cause:
An error occurred because the component had an invalid ID.

Action:
Provide the correct ID value for the application metadata. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00535
cannot change TypeManager associated with a PManager after it is initialized

Category:
Programmatic

Cause:
An attempt was made to associate TypeManager with PManager after it was initialized.

Action:
Contact Oracle Support Services.

MDS-00536
cannot change FileTypeManager associated with a PManager after it is initialized

Category:
Programmatic

Cause:
An attempt was made to associate FileTypeManager with PManager after it was initialized.

Action:
Contact Oracle Support Services.

MDS-00537
unable to rename {0} to {1}

Category:
Data

Cause:
An error occurred during a rename operation.

Action:
Retry the rename operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00538
failure to rename document {0} because metadata store "{1}" is read-only

Category:
Data

Cause:
An error occurred during rename operation because the metadata store was configured as read-only.

Action:
To rename a document, provide a store that can be written to, that is not read-only.

MDS-00539
A document can be renamed only within its source store. The new name {1} in this rename operation does not map to the same store as the old name {0}.

Category:
Programmatic

Cause:
An error occurred during a rename operation. An invalid new name for the rename operation caused the renamed document to be stored in another metadata store.

Action:
Provide a new, valid document name that maps to the same metadata store that contains the original document.

MDS-00541
SAX events cannot be generated for non-XML document {0}.

Category:
Programmatic

Cause:
An attempt was made to generate SAX events for non-XML documents.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00547
The read operation is not supported for packages from Web content from the servlet context.

Category:
Programmatic

Cause:
A read operation was attempted for packages from Web content, which is not supported.

Action:
The read operation is not supported, therefore no action is required.

MDS-00550
Updates across multiple stores are not allowed in the same transaction.

Category:
Programmatic

Cause:
An attempt was made to perform updates across multiple stores in the same transaction.

Action:
Verify that the document is being saved to the same store on which it exists.

MDS-00551
failure to delete package {0} because it is not empty

Category:
Data

Cause:
An attempt was made to delete a package that was not empty.

Action:
Delete the contents of the package to be deleted first, and then retry the operation.

MDS-00552
failure to delete package {0} with directory {1}

Category:
Files

Cause:
An error occurred while deleting the directory for the package.

Action:
Ensure no files from the directory are opened in other applications and retry the operation. Also, refer to the error messages in the application logs for more information on the actual reason for failure.

MDS-00554
Package {0} cannot be found in the specified store.

Category:
Programmatic

Cause:
The requested operation was not completed because the package name that was supplied was invalid.

Action:
Provide a valid package name and retry the operation.

MDS-00555
The partitionName {0} is invalid.

Category:
Programmatic

Cause:
The requested operation was not completed because the partition name that was supplied was invalid.

Action:
Provide a valid partition name and retry the operation.

MDS-00557
Resource {0} is already locked or is being modified.

Category:
Session

Cause:
An attempt was made to modify a document that was already being modified by another user.

Action:
Retry modifying the document after the lock is released by the other users. Also, refer to the error messages in the application logs for more information on the actual reason for failure.

MDS-00558
The partitionName {0} is not available.

Category:
Programmatic

Cause:
No partition with that name existed.

Action:
Provide a partition name that exists.

MDS-00559
A partition with name {0} already exists.

Category:
Programmatic

Cause:
The name provided for creating a new partition was already in use by another partition.

Action:
Provide a different name for the new partition.

MDS-00560
The MDS repository is incompatible with the archive. The repository version is {0} whereas archive version is {1}.

Category:
Upgrade

Cause:
The MDS repository was not compatible with the archive provided.

Action:
Upgrade the target MDS repository or use a compatible archive for the operation.

MDS-00561
The create operation is not supported for metadata stores of type "{0}".

Category:
Configuration

Cause:
An attempt was made to create a new document or package in a read-only metadata store.

Action:
Reconfigure the application to use a writable metadata store.

MDS-00562
The delete operation is not supported for metadata stores of type "{0}".

Category:
Configuration

Cause:
An attempt was made to delete a document from a read-only metadata store.

Action:
Reconfigure the application to use a writable metadata store.

MDS-00563
The save operation is not supported for metadata stores of type "{0}".

Category:
Configuration

Cause:
An attempt was made to save a document to a read-only metadata store.

Action:
Reconfigure the application to use a writable metadata store.

MDS-00564
GUID feature is not supported for metadata stores of type "{0}".

Category:
Configuration

Cause:
An attempt was made to get a document by GUID from a metadata store that does not support GUIDs.

Action:
Reconfigure the application to use a metadata store that supports GUIDs, such as DBMetadataStore.

MDS-00565
The rename operation is not supported for metadata stores of type "{0}".

Category:
Configuration

Cause:
An attempt was made to rename a document or package in a read-only store.

Action:
Reconfigure the application to use a writable metadata store.

MDS-00566
The DOM content is NULL for {0}.

Category:
Data

Cause:
DOM document content provided was null.

Action:
Provide valid DOM content and retry the operation.

MDS-00567
The metadata changes for document "{0}" cannot be written in the underlying store because read-only mode is enabled in the configuration.

Category:
Configuration

Cause:
An attempt to change metadata was made while changes were disabled for maintenance operations.

Action:
Reconfigure the application to not specify read-only mode in the configuration and use a writable metadata store to persist metadata changes.

MDS-00568
MetadataStore initialization failure because "{0}" is invalid

Category:
Files

Cause:
The URL store mapping was invalid.

Action:
Provide a valid URL store mapping.

MDS-00569
unable to read document {0} from "{1}"

Category:
Data

Cause:
There was an error reading the document from the configured metadata store.

Action:
Retry the operation. If the problem persists, verify that the document exists in the configured metadata store.

MDS-00570
The name or content exceeds the MDS repository schema size for {0}.

Category:
Data

Cause:
The metadata name or the content exceeded the schema size.

Action:
Reduce the length of the metadata name or content, and then retry the operation. Refer to the documentation for the allowed sizes for names and content.

MDS-00571
The bean content is NULL for {0}.

Category:
Data

Cause:
The bean content was null.

Action:
Provide valid bean content, and then retry the operation.

MDS-00572
failure to get the ConnectionManager because the DBContext is null

Category:
Programmatic

Cause:
The DBContext value is null. Also, using any MetadataStore, PManager, or MDSInstance that has already been released might lead to this error.

Action:
Do not use any metadata store, PManager, or MDSInstance that is already released.

MDS-00573
The metadata store is already associated with a PManager.

Category:
Programmatic

Cause:
The PConfig provided for creating the PManager or MDSInstance was already used by another PManager or MDSInstance.

Action:
Provide a new PConfig when creating the PManager or MDSInstance.

MDS-00574
The document {0} does not exist in the configured metadata store.

Category:
Data

Cause:
The document being locked did not exist in the configured metadata store.

Action:
Ensure that the document to be locked exists, and that the name of the document is correct.

MDS-00575
failure to acquire write lock for {0}

Category:
Data

Cause:
An attempt to acquire a write lock for a document failed.

Action:
Refer to the cause exception message in application logs for details on the actual cause of the failure.

MDS-00576
failure to process {0} because metadata store "{1}" is read-only

Category:
Configuration

Cause:
An attempt was made to modify metadata in a read-only metadata store.

Action:
Provide a writable metadata store to allow modification of the document.

MDS-00577
Could not acquire read/write lock for {0} within the default waiting time interval

Category:
Files

Cause:
Read/Write lock could not be obtained for a file within the waiting time interval.

Action:
Try the operation again after some time.

MDS-00578
Failed to process document {0} due to a critical error writing to the repository

Category:
Configuration

Cause:
A critical error occurred while the metadata document was being written to the repository.

Action:
Contact the application administrator with cause exception message details to resolve the repository error.

MDS-00579
The document {0} does not have version {1} in the repository.

Category:
Data

Cause:
Specified version does not exist for the document.

Action:
Provide an existing version for the document.

MDS-00580
operation failed for {0} because no metadata-store was defined in the configuration for metadata-store-usage {0}.

Category:
Configuration

Cause:
incomplete configuration, no metadata-store was defined for the metadata-store-usage

Action:
Define the metadataStore for the empty metadata-store-usage.

MDS-00581
error deleting partition {0} in file repository {1}

Category:
Configuration

Cause:
The directory represented by the file repository or partition is read only.

Action:
Verify that the metadata path to the repository and partition exist and are writable.

MDS-00582
The MetadataStore {0} is writable but does override getMetadataStoreCommunicator() method.

Category:
Programmatic

Cause:
Configuration used a MetadataStore that was writable but not supporting MetadataStoreCommunicator interface.

Action:
Override getMetadataStoreCommunicator() in the MetadataStore class to return an appropriate MetadataStoreCommunicator instance.

MDS-00583
Could not release read/write lock for {0} because the lock was not found.

Category:
Files

Cause:
Read/Write lock could not be released because it was already removed from the lock cache.

Action:
Contact Oracle Support Services.

MDS-00584
The MDS repository's database platform is different that of the archive. The repository's database platform is {1} whereas the archive's platform is {0}.

Category:
Data

Cause:
The MDS repository platform was not compatible with the archive provided.

Action:
Use a platform compatible archive for the operation.

MDS-00585
Failure to create deployment lineage because metadata store "{0}" is read-only

Category:
Configuration

Cause:
An attempt was made to create deployment lineage in a read-only metadata store. Deployment lineage in repository represents Application name and MAR module name.

Action:
Configure a metadata store that supports deployment management, typically a DBMetadataStore.

MDS-00586
ArchiveMetadataStore is restricted to be used with MDS Transfer operation only. Reading or writing files in ArchiveMetadataStore is not supported outside of transfer.

Category:
Configuration

Cause:
An attempt was made to read or write files in ArchiveMetadataStore outside of transfer.

Action:
ArchiveMetadataStore is not supported outside of transfer. Either use this ArchiveMetadataStore for MDS transfer operation or use some other MetadataStore to store your files.

MDS-00588
Cannot replace the original archive file {0} with the final archive file {1} because the final archive file could not be renamed to {0}.

Category:
Data

Cause:
The final archive file could not be renamed to the original archive file name.

Action:
Look at the cause exception for more details and take corresponding actions.

MDS-00589
Error occurred while creating the final archive file {0}.

Category:
Data

Cause:
Some exception occurred while creating the final archive.

Action:
Look at the cause exception for more details and take corresponding actions.

MDS-00590
Error occurred while opening or closing the input/output stream for archive file {0}.

Category:
Data

Cause:
Some exception occurred while opening or closing the input/output stream for archive file.

Action:
Look at the cause exception for more details and take corresponding actions.

MDS-00591
"{0}" operation is not supported in ArchiveMetadataStore.

Category:
Data

Cause:
An unsupported operation has been attempted in ArchiveMetadataStore.

Action:
Look at the ArchiveMetadataStore javadoc for supported operations.

MDS-00592
Error occurred while initializing FileMetadataStore connection for the temporary directory.

Category:
Data

Cause:
An error occurred while initializing the FileMetadataStore connection for the temporary directory.

Action:
Look at the cause exception for more details and take corresponding actions.

MDS-00593
Unable to read the file {0} from archive {1}.

Category:
Data

Cause:
Some I/O Exception occurred while reading the given file from archive.

Action:
Look at the cause exception for more details and take corresponding actions.

MDS-00594
Unable to write the file {0} to archive {1}.

Category:
Data

Cause:
Some I/O Exception occurred while writing the given file to archive.

Action:
Look at the cause exception for more details and take corresponding actions.

MDS-00595
The parent directory {0} given in archive file path does not exist. Cannot create ArchiveMetadataStore for the archive file {1}.

Category:
Data

Cause:
The parent directory mentioned in archive file path does not exist.

Action:
Provide valid parent directory in archive file path to create ArchiveMetadataStore.

MDS-00596
Failure to read document {0} because it is not found in "{1}"

Category:
Data

Cause:
The document to be read was not found.

Action:
Verify that the document exists in the ArchiveMetadataStore before reading the document.

MDS-00597
Failure to open the archive file {0}. Cannot create ArchiveMetadataStore for the archive file {0}.

Category:
Data

Cause:
Could not open the given archive file.

Action:
Try creating ArchiveMetadata store with a valid archive file.

MDS-00598
Cannot create an intermediary archive during export to the archive file {0}.

Category:
Data

Cause:
Either the intermediary archive file could not be created in the default temporary-file directory or an I/O error occurred.

Action:
Look at the cause exception for more details and take action accordingly.

MDS-00599
Cannot obtain a connection to the Archive Metadata Store for archive file {0}.

Category:
Programmatic

Cause:
There was a problem obtaining a connection to the Archive Metadata Store.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00601
The XLIFF document has invalid target language {0}.

Category:
Data

Cause:
The target language specified was either null or empty.

Action:
Specify a valid target language and retry the operation.

MDS-00703
The name {0} is not a valid name under package {1} because {2} resource not considered child of the package.

Category:
Data

Cause:
A specified child resource was not a child of the package.

Action:
Specify a valid child resource name, and then retry the operation.

MDS-00704
invalid value {0} for property {1} on component {2}

Category:
Configuration

Cause:
An invalid property value was provided.

Action:
Provide a valid property value and retry.

MDS-00771
A component with {0} "{1}" already exists.

Category:
Data

Cause:
The specified component already existed.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-00907
unable to save document "{0}" because either a document or package of the same name already exists

Category:
Data

Cause:
A document or package with the same name already existed in the repository, perhaps because it was just created by another user.

Action:
Retry the operation. If necessary, choose another name for the object being saved.

MDS-00908
unable to create package "{0}" because a document or package of the same name already exists

Category:
Data

Cause:
A document or package with the same name already existed in the repository, perhaps because it was just created by another user.

Action:
Retry the operation. If necessary choose another name for the object being saved.

MDS-00910
unable to save the document because of corrupt MDS database sequences or other internal errors.

Category:
Data

Cause:
The database sequence used for generating the unique document ID was corrupt or some other internal errors caused violation of unique constraints.

Action:
Retry the operation after deploying metadata to another MDS database repository partition. If that still fails, contact Oracle Support Services.

MDS-00911
Document with name "{0}" and version {1} [Low CN={2}, High CN={3}] does not exist in the repository.

Category:
Data

Cause:
The document was not found in the MDS repository.

Action:
Specify a correct name for the document and retry the operation. Check if the document is deleted by another user.

MDS-00912
MDS repository is incompatible with the middle tier. Repository version "{0}" is older than minimum repository version "{1}" required.

Category:
Upgrade

Cause:
The MDS repository was older than minimum version required by the middle tier.

Action:
Upgrade the MDS repository to the required version.

MDS-00913
MDS repository is incompatible with the middle tier. MDS version "{0}" is older than minimum MDS version "{1}".

Category:
Upgrade

Cause:
The MDS version was older than the minimum required version for using the MDS repository.

Action:
Upgrade the MDS library to the required version.

MDS-00914
unable to save document "{0}" because either an already deleted document or package with conflicting name or type already exists

Category:
Data

Cause:
A document or package with the same name or a parent package of incorrect type already existed in the repository as a deleted version.

Action:
Delete the conflicting resource from repository or check if the new resource is invalid. If necessary, choose another name for the object being saved.

MDS-00915
MDS repository is incompatible with the middle tier for dumping or restoring metadata.

Category:
Upgrade

Cause:
The MDS repository was older than minimum version required by the middle tier to dump or restore metadata.

Action:
Retry the operation after upgrading the MDS repository to newer version or use compatible middle tier to perform the operation.

MDS-00916
MetadataStore configured for {0} does not support deployment management.

Category:
Configuration

Cause:
The metadata store configured for the resource did not support deployment management.

Action:
Deployment management is supported in MDS repository version 11.1.1.4.0 (11gR1 PS3 patchset) onwards. Upgrade the repository to this version or later.

MDS-00918
Connection details for the MDS repository are incomplete. The values for "{0}" are invalid

Category:
Configuration

Cause:
The MDS repository connection details were invalid or missing.

Action:
Specify correct values for the MDS repository details in the configuration and retry the operation.

MDS-00919
Internal error: The database context for this repository appears to be corrupt.

Category:
Configuration

Cause:
The database context was invalid.

Action:
Verify that the repository details are correct in the configuration.

MDS-00922
The ConnectionManager "{0}" cannot be instantiated.

Category:
Configuration

Cause:
There was an error instantiating the ConnnectionManager class

Action:
Contact Oracle Support Services.

MDS-00923
Unable to create sandbox "{0}"

Category:
Data

Cause:
An error occurred during creation of sandbox.

Action:
Look in the error message log for the exact reason for the failure.

MDS-00928
Invalid document reference, package "cust" should appear before package "trans" in the names of customization translation documents.

Category:
Data

Cause:
An internal MDS document (one in package mdssys) was found with an invalid name, or an attempt was made to create a name object with such an invalid name.

Action:
Avoid using package or document names containing path element "mdssys" which is reserved for internal MDS use. If necessary, remove such invalid documents from the metadata store.

MDS-00929
unable to look up name "{0}" in JNDI context

Category:
Configuration

Cause:
The implementation class to use for initial context was not found.

Action:
Verify that environment properties are configured using system properties or application resources files.

MDS-00930
The JNDI location details for the registered datasource are incomplete.

Category:
Configuration

Cause:
JNDI location details were found to be incomplete.

Action:
Provide complete JNDI location information in the configuration.

MDS-00931
The database version is {0}.{1}, but MDS requires at least {2}.{3}.

Category:
Upgrade

Cause:
The database version is older than the minimum database version required for hosting MDS repository.

Action:
Upgrade the database to the minimum required version. Contact the database administrator for assistance.

MDS-00932
unknown database vendor {0}

Category:
Installation

Cause:
The database vendor could not be identified.

Action:
Verify that the MDS repository is hosted on supported database vendors.

MDS-00933
cannot create data source using URL "{0}"

Category:
Configuration

Cause:
An error occurred while creating the data source using the specified URL.

Action:
Verify that the URL specified is correct and retry the operation.

MDS-00934
XDB is not supported on database platform {0}.

Category:
Programmatic

Cause:
An attempt was made to store XML metadata in a non-XDB database.

Action:
Verify that the correct MDS repository is being used.

MDS-00935
Unable to complete operation even after maximum connection retries ({0}).

Category:
High Availability

Cause:
An error occurred while performing operation.

Action:
Ensure that the database is running. Retry the operation later.

MDS-00936
Fast Connection Failover is not supported on the underlying database connection ({0}).

Category:
High Availability

Cause:
The underlying database connection did not support fast connection failover, and retry-connection was set to true in either the config file, or programmatically.

Action:
Either stop and then restart the database connection and configure it to allow fast connection failover, or do not attempt to set retry-connection to true.

MDS-00937
A local transaction operation like commit or rollback cannot be used in a global transaction on connection "{0}".

Category:
Configuration

Cause:
The database connection was configured for global transactions, but MDS was not configured to support global transactions.

Action:
Reconfigure the database connection to use local transactions. Change "tx-level" attribute on the MDS datasource to "local".

MDS-00938
Unable to get an ADF library class loader

Category:
Data

Cause:
MDS expects to retrieve a resource from an ADF library, but is unable to obtain an ADF library classloader.

Action:
Consider whether the resource should be repackaged in an ADF library rather than an ordinary jar.

MDS-01059
document with the name {0} missing in the source metadata store

Category:
Data

Cause:
The document to be transferred did not exist in the source metadata store.

Action:
Verify that the document name is correct, and that it exists in the source metadata store.

MDS-01061
Listener {0} cannot be instantiated.

Category:
Configuration

Cause:
The listener class did not exist.

Action:
Verify that the name of the listener class is correct. Ensure that the class is available on the class path.

MDS-01104
finding no documents for processing that match the pattern provided

Category:
Data

Cause:
No documents were found on the source metadata store that matched the pattern provided, or that matched the document name.

Action:
Provide another pattern or document name, or provide another metadata store in which to look for the documents.

MDS-01105
invalid label {0}

Category:
Data

Cause:
The label specified for the source metadata store did not exist.

Action:
Verify that the label name is correct, or provide a label that exists in the source metadata store.

MDS-01106
The TransferTypeRestriction {0} cannot be associated with given TransferType {1}.

Category:
Programmatic

Cause:
The given TransferTypeRestriction cannot be associated with the specified TransferType.

Action:
Ensure that given TransferTypeRestriction is valid for the specified TransferType.

MDS-01107
Post transfer label cannot be created in target store.

Category:
Data

Cause:
Post transfer label cannot be created in the target store. Examine the cause exception messages to find the root cause of it.

Action:
Examine any accompanying messages to decide if further action is required.

MDS-01108
TransferType cannot be null for ExtendedTransferType.

Category:
Data

Cause:
TransferType provided to create ExtendedTransferType was null.

Action:
Provide valid TransferType to create ExtendedTransferType.

MDS-01109
The target archive configured in ArchiveMetadataStore already exists. Cannot export the documents into an existing archive file.

Category:
Data

Cause:
The target archive already exists. Exporting the documents into an existing archive is not allowed.

Action:
Export the documents into a non existing archive file.

MDS-01110
Sandbox export operation allowed only from a database metadata store to an archive metadata store.

Category:
Configuration

Cause:
Either source metadata store is not a database or the target metadata store is not an archive in sandbox export operation.

Action:
Configure source metadata store to be a database and target metadata store to be an archive in sandbox export operation.

MDS-01111
Sandbox import operation allowed only from Archive Metadata Store to a Database Metadata store.

Category:
Configuration

Cause:
Either source metadata store is not an archive metadata store or the target metadata store is not a database in sandbox import operation.

Action:
Configure source metadata store to be an archive metadata store and target metadata store to be a database in sandbox import operation.

MDS-01112
Transfer unit list in a Sandbox export/import operation should have at least one transfer unit.

Category:
Data

Cause:
Transfer unit list in Sandbox export/import operation empty.

Action:
Ensure that there is at least one transfer unit to be transferred in sandbox export/import operation.

MDS-01113
Sandbox metadata file required for import to a new sandbox operation.

Category:
Data

Cause:
Sandbox metadata file missing in source Archive metadata store in import to a new sandbox operation.

Action:
Import to a new sandbox only from an archive store whose contents were exported from a sandbox and contain sandbox metadata document.

MDS-01114
Sandbox with same name as the one imported in a sandbox import operation exists on the target metadata store.

Category:
Programmatic

Cause:
Sandbox with same name already exists on the target metadata store and the flag to force creation of sandbox is not set to true.

Action:
Pass true for forceSBCreation to TransferParams.createForSandboxImport() or destroy sandbox already existing with same name on the target metadata store in sandbox import operation.

MDS-01115
Source sandbox in a sandbox export operation does not contain metadata.

Category:
Programmatic

Cause:
Source sandbox in export operation was not created with metadata.

Action:
Export from a Sandbox that was created with metadata.

MDS-01116
Existing target sandbox in import operation does not contain metadata.

Category:
Programmatic

Cause:
Target sandbox in an import into an existing sandbox operation was not created with metadata.

Action:
Import into an existing sandbox that was created with metadata.

MDS-01117
Sandbox archive imported into an existing sandbox.

Category:
Programmatic

Cause:
The archive imported into an existing sandbox contains sandbox metadata.

Action:
Import only regular archives(that do not contain sandbox metadata) into an existing sandbox.

MDS-01118
Sandbox export operation not supported because the source MDS database repository is of older version that does not support this feature.

Category:
Configuration

Cause:
Sandbox metadata is needed to transfer documents from sandbox. Source store being used does not support storing metadata for sandbox.

Action:
Sandbox metadata is supported in MDS repository version 11.1.1.4.0 (11gR1 PS3 patchset) onwards. Upgrade the repository to this version or later.

MDS-01119
Sandbox import operation not supported because the target MDS database repository is of older version that does not support this feature.

Category:
Configuration

Cause:
Sandbox metadata is needed to transfer documents from sandbox. But target store being used does not support storing metadata for sandbox.

Action:
Sandbox metadata is supported in MDS repository version 11.1.1.4.0 (11gR1 PS3 patchset) onwards. Upgrade the repository to this version or later.

MDS-01120
Sandbox transfer unit list creation not supported because the source MDS database repository is of older version that does not support this feature.

Category:
Configuration

Cause:
Sandbox metadata is needed to transfer documents from sandbox. Source store being used does not support storing metadata for sandbox.

Action:
Sandbox metadata is supported in MDS repository version 11.1.1.4.0 (11gR1 PS3 patchset) onwards. Upgrade the repository to this version or later.

MDS-01121
Document "mds-transfer-config.xml" cannot be read by MDSTransfer.

Category:
Data

Cause:
The /meta-inf/mds-transfer-config.xml document cannot be read from source store. Refer to cause exception for more information on the actual reason for failure.

Action:
Look for messages that describe the cause exception, and then take the appropriate action.

MDS-01122
Metadata Object Name "{0}" specified in the mds-transfer-config.xml to preserve user updated documents in target repository is not a valid metadata object name.

Category:
Data

Cause:
Metadata object name specified in /meta-inf/mds-transfer-config.xml to preserve user updated documents in target repository is not a valid metadata object name.

Action:
Make sure the document name specified in mds-transfer-config.xml is a valid metadata object name but not a special document name.

MDS-01123
The metadata path "{0}" specified in the mds-transfer-config.xml to preserve user updated documents in target repository is not a valid metadata path.

Category:
Data

Cause:
The metadata path specified in /meta-inf/mds-transfer-config.xml to preserve the user updated documents in target repository is not a valid metadata path.

Action:
Make sure the metadata path specified in mds-transfer-config.xml is a valid metadata path.

MDS-01150
Reference is null or empty.

Category:
Programmatic

Cause:
A reference value was null or empty.

Action:
Use a valid reference value that is not empty or null.

MDS-01151
Id/LocationPath reference is null or missing.

Category:
Programmatic

Cause:
An Id/LocationPath reference value was null or empty.

Action:
Use a valid Id/LocationPath reference value that is not empty or null.

MDS-01153
invalid LocationPath expression "{0}"

Category:
Programmatic

Cause:
The LocationPath expression was invalid.

Action:
Use a valid LocationPath format. The LocationPath expression should follow the format "/text()" or "/text()[x]", where 'x' is the index of "text block".

MDS-01154
invalid LocationPath expression "{0}"

Category:
Programmatic

Cause:
The node index in the LocationPath expression was invalid.

Action:
Change the node index in the LocationPath expression to a number greater than or equal to 1.

MDS-01158
Expecting a base document. Reference "{0}" is a special document.

Category:
Programmatic

Cause:
A base document was expected, but the reference was a special document.

Action:
Use a valid base document.

MDS-01159
Expecting absolute document reference. Reference "{0}" has local element reference portion.

Category:
Programmatic

Cause:
The supplied reference was not the expected type.

Action:
Ensure the reference is of the expected type.

MDS-01160
Expecting absolute document reference. Reference "{0}" is a relative reference to the document.

Category:
Programmatic

Cause:
The supplied reference was not the expected type.

Action:
Ensure the reference is of the expected type.

MDS-01161
Reference "{0}" has an invalid character "{1}".

Category:
Programmatic

Cause:
The supplied reference did not follow the MDS naming standard.

Action:
Use valid characters for the reference.

MDS-01162
Reference "{0}" has an invalid XML attribute character.

Category:
Programmatic

Cause:
The supplied reference did not follow the MDS naming standard.

Action:
Use valid characters for the reference.

MDS-01163
invalid reference "{0}"

Category:
Programmatic

Cause:
The supplied reference did not follow the MDS naming standard.

Action:
Ensure that the reference follows the MDS naming standard.

MDS-01164
invalid reference "{0}" for a translation document

Category:
Programmatic

Cause:
The supplied reference did not have the expected document extension (.xlf).

Action:
Use the correct extension, .xlf, for the translation document.

MDS-01165
invalid reference "{0}" for a customization document

Category:
Programmatic

Cause:
The supplied reference did not have the expected document extension (.xml or .lso).

Action:
Use the correct extension for the customization document, .xml for MetadataObject or .lso for StreamedObject.

MDS-01166
invalid reference "{0}" for a metadata extension document

Category:
Programmatic

Cause:
The supplied reference did not have the expected document extension (.rdf).

Action:
Use the correct extension, .rdf, for the metadata extension document.

MDS-01167
There is no namespace declaration for the prefix "{1}" used in LocationPath expression "{0}".

Category:
Programmatic

Cause:
The LocationPath expression was incomplete.

Action:
Use a valid LocationPath format.

MDS-01168
Partition name "{0}" starts or ends with character "{1}". Partition name cannot contain leading or trailing spaces, ".", "-"

Category:
Configuration

Cause:
The supplied partition name contained leading or trailing spaces, ".", "-".

Action:
Ensure that the partition name follows the MDS naming standard for partitions.

MDS-01169
Partition name "{0}" has an invalid character "{1}".

Category:
Configuration

Cause:
The supplied partition name did not follow the MDS naming standard.

Action:
Use valid characters for the partition name.

MDS-01170
Partition name is null or empty.

Category:
Configuration

Cause:
Partition name value was null or empty.

Action:
Use a valid partition name that is not empty or null.

MDS-01171
The ID prefix generated by concatenating the layer name "{0}" and layer value "{1}" is not a valid MDS ID.

Category:
Programmatic

Cause:
The ID prefix generated by concatenating the layer name with layer value did not follow the MDS ID naming standard.

Action:
Ensure that the ID prefix generated by concatenating the layer name with layer value follows the MDS ID naming standard.

MDS-01200
This operation is not supported.

Category:
Programmatic

Cause:
An MDS query operation was attempted, but this particular operation is not supported.

Action:
Note the stack backtrace and context of the operation, and contact Oracle Support Services.

MDS-01201
An invalid parameter cannot be used when constructing a query condition.

Category:
Programmatic

Cause:
An invalid parameter was passed to the class ConditionFactory.

Action:
Note the stack backtrace and context of the operation, and contact Oracle Support Services.

MDS-01205
A SQL error is occurring when performing the query: "{0}" with binds {1}.

Category:
Programmatic

Cause:
An MDS query on a database store led to a SQL error.

Action:
Note the stack backtrace and context of the operation, including the reported SQL query and error, and contact Oracle Support Services.

MDS-01206
The array size for the query must be greater than zero.

Category:
Programmatic

Cause:
An MDS query specified a fetch unit size that was not positive.

Action:
Note the stack backtrace and context of the operation and contact Oracle Support Services.

MDS-01207
The namespace mapping for the prefix "{0}" specified in the location path, is missing.

Category:
Configuration

Cause:
During XPath evaluation, the namespace prefix was used, but the prefix was not mapped to a namespace.

Action:
Note the stack backtrace and context of the operation and contact Oracle Support Services.

MDS-01208
MDS query condition produces more than {0} characters of SQL where clause.

Category:
Programmatic

Cause:
An MDS query condition was so large that it would produce a very large SQL statement.

Action:
Note the stack backtrace and context of the operation, and contact Oracle Support Services.

MDS-01209
The exclusion CustLayerFilter for layer {0} cannot contain another exclusion CustLayerFilter.

Category:
Programmatic

Cause:
An exclusion CustLayerFilter is nested in another exclusion CustLayterFilter.

Action:
Do not include an exclusion CustLayerFilter inside another exclusion CustLayerFitler.

MDS-01250
The file path "{0}" does not exist.

Category:
Files

Cause:
An invalid path was provided.

Action:
Retry the operation with a valid file path.

MDS-01251
The parameter file {0} has no namespace on the document element.

Category:
Data

Cause:
A namespace was missing from the parameter file provided.

Action:
Provide a parameter file with valid namespace information.

MDS-01252
The parameter file {0} must have either {1} or {2} definition.

Category:
Data

Cause:
No source stores or target stores information were provided in the parameter file.

Action:
Check the parameter file to have source and target store information and retry.

MDS-01253
The parameter file {0} must not have both {1} and {2} definitions.

Category:
Data

Cause:
An attempt was made to transfer from source directory to target directory. Both source and target as directories is not supported.

Action:
Provide correct source and target definition. Either source or target should be a metadata store.

MDS-01254
The parameter file {0} contains same store definition for sourceStore and targetStore.

Category:
Data

Cause:
An attempt was made to transfer from and to the same store. The definition for sourceStore cannot be the same as the definition for targetStore.

Action:
Provide correct source and target information. Change either source or target store definition.

MDS-01255
The property {0} has not been supplied.

Category:
Data

Cause:
The required property was missing from the parameter file.

Action:
Check the parameter file and supply the required property. Refer to the MDS documentation for the correct syntax. A sample parameter file is also part of documentation.

MDS-01258
The value {0} for property {1} is invalid.

Category:
Data

Cause:
An invalid property value was provided in the parameter file.

Action:
Provide a valid property value. Refer to the MDS documentation for the correct syntax. A sample parameter file is also part of documentation.

MDS-01259
The metadata store "{0}" cannot be instantiated.

Category:
Data

Cause:
An error occurred during the instantiation of the class for the metadata store.

Action:
Verify that correct values are provided in the parameter file. Refer to the error messages in application logs that describe the cause exception for more information on the actual reason for failure.

MDS-01260
failure to process command-line arguments

Category:
Data

Cause:
Invalid command-line parameters were provided.

Action:
Provide valid command-line parameters, and retry the operation. Refer to the MDS documentation for syntax of the tool parameters, or run the tool without parameters in order to get the Help message.

MDS-01262
failure of transfer operation on a read-only target metadata store

Category:
Configuration

Cause:
The target metadata store used for transfer was read-only, for example a classpath store.

Action:
Provide a writable target metadata store.

MDS-01263
operation failure on the resource {0} because source metadata store is read-only

Category:
Configuration

Cause:
An attempt was made to delete, create, update or get a mutable metadata object from a read-only source metadata store.

Action:
Provide a writable source metadata store.

MDS-01264
The given element must contain either "customization" or "translation" configuration.

Category:
Configuration

Cause:
A customization or a translation configuration was missing for an element.

Action:
Examine the transfer parameter file for valid MDS configuration.

MDS-01265
Invalid parameter file {0}. Reason: <{1}:{2}> {3}

Category:
Files

Cause:
Parameter file provided was not valid.

Action:
Provide a valid parameter file. Refer to the MDS documentation for the correct syntax. A sample parameter file is also part of documentation. Refer to sample parameter for correct syntax.

MDS-01266
The associated customization document is missing for a given customization class {0} for the given document name {1}.

Category:
Data

Cause:
The associated customization document for the given customization class did not exist.

Action:
If the associated customization document was to be transferred, verify that it exists. Otherwise, no action is required.

MDS-01267
The associated translation document is not found for a given locale {0} for the given document name {1}.

Category:
Data

Cause:
Associated translation document did not exist for the given locale.

Action:
If the associated translation document was expected to be transferred, verify if it exists, otherwise, no action required.

MDS-01268
The associated extended metadata document for the given document name {0} is missing.

Category:
Data

Cause:
No associated extended metadata document for the given document name existed.

Action:
If the document was to be transferred, verify that the document exists. Otherwise, no action is required.

MDS-01270
Opening and closing parentheses do not match.

Category:
Configuration

Cause:
Either an opening or closing parentheses was missing.

Action:
Check and correct the namespace mappings provided. Each opening parentheses should have an equivalent closing parentheses and vice versa.

MDS-01271
Cannot get the dependency registry

Category:
Configuration

Cause:
An error occurred while getting the dependency registry.

Action:
Retry the operation. If the problem persists, look for messages that describe the cause exception for more information on the actual reason for failure.

MDS-01272
unable to read mds-webapp-config.xml file

Category:
Files

Cause:
The mds-webapp-config.xml file was invalid.

Action:
Confirm that the mds-webapp-config.xml file for the application is well formed, and valid.

MDS-01273
The operation on the resource {0} failed because source metadata store mapped to the namespace {1} is read only.

Category:
Configuration

Cause:
An attempt was made to delete, create, update or get a mutable metadata object from a readonly source metadata store.

Action:
Provide a writable source metadata store.

MDS-01301
Element "{1}", namespace "{0}" is not a valid child under parent "{3}", namespace "{2}".

Category:
Programmatic

Cause:
An attempt was made to add, insert or replace a child element of the wrong type.

Action:
Check the schema definition and ensure that the child element is the correct type.

MDS-01302
failure to load schema file "{0}"

Category:
Data

Cause:
An exception occurred in the XMLEF layer during processing of the schema definitions.

Action:
Look for messages that describe the cause exception, and then take the appropriate action.

MDS-01303
failure to register grammar from schema file "{0}"

Category:
Data

Cause:
An exception occurred in the XMLEF layer during addition of schema definitions.

Action:
Look for messages that describe the cause exception, and then take the appropriate action.

MDS-01305
failure to locate schema file "{0}".

Category:
Configuration

Cause:
The schema definition file was not found.

Action:
Verify that the schema file name is correct, and that it is in the correct location.

MDS-01306
Grammar from a Web application can be added only once.

Category:
Configuration

Cause:
There were multiple method calls to add grammar from a web application.

Action:
Verify that a grammar definition has already been added for the given MDSInstance and ServletContext. If it has then remove the calls to add it multiple times.

MDS-01307
no schema files for processing

Category:
Programmatic

Cause:
No schema files were found against which beans can be generated.

Action:
Pass an existing schema file to the bean generator.

MDS-01308
Event "{0}" is not supported.

Category:
Programmatic

Cause:
An attempt was made to use event types that are not supported for the selected content model.

Action:
Use only the event types that are allowed for the selected content model.

MDS-01309
ContentModelPipeline is empty.

Category:
Programmatic

Cause:
The contentModelPipeline contained an empty or null builder list.

Action:
A list of one or more valid builders must be available in the ContentModelPipeline.

MDS-01310
Invalid ContentModelPipeline. Missing {0}.

Category:
Programmatic

Cause:
The expected builder was not available in builder list of the ContentModelPipeline.

Action:
Valid builders must be supplied to the ContentModelPipeline.

MDS-01311
The DOM tree does not support the DOM event model.

Category:
Programmatic

Cause:
This DOM Document did not implement EventTarget interface.

Action:
Verify whether the Oracle XML Developer's Kit is used.

MDS-01312
Change-list transaction state is invalid.

Category:
Programmatic

Cause:
The current change-list transaction state is invalid for the customization operation performed.

Action:
Ensure Change-list to be in valid transaction state to perform the necessary customization operation.

MDS-01313
The argument for document cannot be null.

Category:
Data

Cause:
The argument for DocumentName was null.

Action:
Provide a valid DocumentName.

MDS-01314
TypeAnnotationProvider cannot be null.

Category:
Data

Cause:
The argument for TypeAnnotationProvider was null.

Action:
Provide a valid TypeAnnotationProvider.

MDS-01316
Support for XPath is not implemented yet.

Category:
Configuration

Cause:
Support for XPath has not been implemented yet.

Action:
Provide a valid Configurable ID.

MDS-01319
JAXP support is not available. Falling back to using Oracle XML Developer's Kit for parsing the document {0}.

Category:
Configuration

Cause:
JAXP support was not available.

Action:
None.

MDS-01320
Modifying the prefix declaration for {0} from "{1}" to "{2}" in document {3} through customizations is not supported.

Category:
Programmatic

Cause:
An attempt was made to change an existing prefix declaration.

Action:
Avoid attempts to change existing prefix declarations.

MDS-01321
Node type should be one of ImmutableModelNode.ELEMENT or ImmutableModelNode.TEXT or ImmutableModelNode.CDATA.

Category:
Data

Cause:
The node was not of the type ImmutableModelNode.ELEMENT or ImmutableModelNode.TEXT or ImmutableModelNode.CDATA.

Action:
Ensure the node type is one of the following types: ImmutableModelNode.ELEMENT or ImmutableModelNode.TEXT or ImmutableModelNode.CDATA.

MDS-01322
Value "{0}" does not satisfy "{1}" type.

Category:
Data

Cause:
The data type conversion failed.

Action:
Verify that the expected XSD built-in simple data type and the passed-in string value are convertible.

MDS-01323
Value "{0}" has an incorrect number of characters for a base64Binary.

Category:
Data

Cause:
The value did not represent a valid Base64Binary.

Action:
Verify that the input value is valid.

MDS-01324
Unknown XML schema built-in type "{0}"

Category:
Data

Cause:
An attempt was made to use an unknown XML schema built-in type.

Action:
Use only valid XML schema built-in types.

MDS-01325
unable to load type definition "{0}"

Category:
Configuration

Cause:
Could not load this type definition because the specified location did not exist.

Action:
Ensure that the specified location for the type definition exists.

MDS-01326
Loading of type definition from element "{0}" is not supported.

Category:
Configuration

Cause:
An attempt was made to load a type definition from the specified element that is not supported in the MDS configuration.

Action:
Examine the schema definition to ensure that the entry specified in type definition is correct.

MDS-01327
unable to load data from "{0}" into {1}

Category:
Configuration

Cause:
An error occurred while loading the content of this configuration element.

Action:
Examine the schema definition to ensure that the content of this configuration element is correct.

MDS-01328
unable to load element "{0}" into {1}

Category:
Configuration

Cause:
An error occurred while loading this configuration element.

Action:
Examine the schema definition to ensure this configuration element is correctly specified in the MDS configuration.

MDS-01329
unable to load element "{0}"

Category:
Configuration

Cause:
An error occurred while loading this configuration element.

Action:
Examine the schema definition to ensure this configuration element is correctly specified in the MDS configuration.

MDS-01330
unable to load MDS configuration document

Category:
Files

Cause:
An I/O or parsing error occurred while loading the MDS configuration document.

Action:
Verify that the URL is correct, and ensure that the document contains valid MDS configuration information.

MDS-01331
unable to load MDS configuration document "{0}"

Category:
Files

Cause:
An error occurred in loading the content of MDS configuration document.

Action:
Verify that the URL is correct, and ensure that the document contains valid MDS configuration information.

MDS-01332
Class {0} is not a subclass or implementation of {1}.

Category:
Configuration

Cause:
The class specified in the configuration information did not extend the required class, or implement the required interface.

Action:
Ensure that the class specified in the configuration information extends the correct class, or implements the correct interface.

MDS-01333
missing element "{0}"

Category:
Configuration

Cause:
This element was missing from the MDS configuration information.

Action:
Ensure that the element is specified in the configuration information.

MDS-01334
missing element "{0}" in document "{1}"

Category:
Configuration

Cause:
This element was missing from the MDS configuration information.

Action:
Ensure that this element is specified in the configuration document.

MDS-01335
namespace "{0}" mapped to metadata-store-usage "{1}" but its definition was not found in MDS configuration.

Category:
Configuration

Cause:
Metadata-store-usage element that was referenced by a namespace not found in MDS configuration.

Action:
Ensure that this element is specified in MDS configuration.

MDS-01336
No XML element is provided to create {0}.

Category:
Configuration

Cause:
A null XML element was passed to the constructor of this configuration object.

Action:
Ensure that a valid XML element is provided to create a new instance of this configuration.

MDS-01337
No URL is provided to create {0}.

Category:
Configuration

Cause:
A null URL was passed to the constructor of this configuration object.

Action:
Ensure that a valid URL is provided to create a new instance of this configuration.

MDS-01340
More than one metadata store can be resolved for the namespace "{0}".

Category:
Configuration

Cause:
There were multiple namespace to metadata store mappings in the persistence configuration that satisfied the request for the metadata store of a given namespace.

Action:
Correct the namespace mapping in persistence configuration to ensure that the namespace is mapped to only one metadata store.

MDS-01341
Namespace mapping for "{0}" is overridden by namespace mapping for "{1}"; and they conflict.

Category:
Configuration

Cause:
A conflicting mapping to this namespace has already been defined in the persistence configuration.

Action:
Correct persistence configuration to ensure that there is no conflicting mapping to this namespace.

MDS-01342
No metadata store is mapped to the namespace "{0}".

Category:
Configuration

Cause:
No namespace mapping could be found in the persistence configuration for the specified namespace.

Action:
Ensure that a correct namespace is passed into the method concerned, or alter the application configuration to define the specified namespace.

MDS-01343
There is a duplicate file extension mapping for "{0}".

Category:
Configuration

Cause:
A mapping to this file extension has already been defined in the file type configuration.

Action:
Remove the duplicate file extension mapping from the file type configuration.

MDS-01344
cannot create {0} due to null parameter

Category:
Configuration

Cause:
A null parameter was passed to the constructor of this configuration object.

Action:
Ensure that a valid parameter is provided to create a new instance of this configuration.

MDS-01346
The given namespace path "{0}" is not a valid path.

Category:
Configuration

Cause:
An invalid path was provided to create a namespace.

Action:
Ensure that a valid path is provided to create a namespace.

MDS-01347
Base restriction is supported only for classpath store or servlet context store: namespace "{0}" mapped to "{1}".

Category:
Configuration

Cause:
The base restriction was specified for a metadata store other than the classpath metadata store and servlet context store.

Action:
Correct the namespace mapping in the configuration to ensure that the base restriction is specified only for the classpath store or servlet context store.

MDS-01348
unable to save configuration document to "{0}"

Category:
Files

Cause:
An I/O error occurred while writing the configuration to a file.

Action:
Check the file system and ensure that the file location is writable.

MDS-01349
unable to read existing configuration document "{0}" to be updated

Category:
Files

Cause:
An I/O or parsing error occurred while reading the configuration file.

Action:
Ensure that the configuration file does exist and has valid contents.

MDS-01350
Adding namespace "{0}" mapped to "{1}" conflicts with existing namespace "{2}" mapped to "{3}".

Category:
Configuration

Cause:
An attempt was made to add a new namespace that conflicted with an existing namespace because it mapped to a different repository.

Action:
Ensure that the new namespace does not map to a different repository if the new namespace is a super-namespace or sub-namespace of existing namespaces.

MDS-01351
Adding namespace "{0}" with "{1}" restriction conflicts with existing namespace "{2}" with "{3}" restriction.

Category:
Configuration

Cause:
An attempt was made to add a new namespace that conflicted with an existing namespace in the namespace restriction.

Action:
Ensure that the new namespace does not conflict with existing namespaces in the namespace restriction if the new namespace is a super-namespace or sub-namespace of existing namespaces.

MDS-01352
Customization configuration with granular mapping "{0}" is unsupported; only the slash, "/", is allowed.

Category:
Configuration

Cause:
An attempt was made to add an invalid namespace mapping of the customization configuration. Only one namespace to customization class list mapping is currently allowed, and that namespace has to be a slash (/).

Action:
Ensure that only the slash (/) is specified in the namespace mapping of the customization configuration.

MDS-01353
unable to retrieve customization layer values from "{0}"

Category:
Files

Cause:
An I/O or parsing error occurred while reading the specified file to retrieve customization layer values.

Action:
Ensure that the file does exist and has valid contents.

MDS-01355
Both TypeConfig parameters contain Grammar Providers. Only one Grammar Provider is allowed.

Category:
Configuration

Cause:
A Grammar Provider was specified in multiple type configuration sources.

Action:
Ensure that only one Grammar Provider is specified in the type Configuration.

MDS-01356
Both TypeConfig parameters contain Metadata Providers. Only one Metadata Provider is allowed.

Category:
Configuration

Cause:
A Metadata Provider was specified in multiple type configuration sources.

Action:
Ensure that only one Metadata Provider is specified in the type Configuration.

MDS-01357
MDS configuration is not compatible with JAXB 1.0.

Category:
Configuration

Cause:
JAXB 1.0 jar file (xml.jar) was found on the classpath before any JAXB 2.0 jar files.

Action:
Ensure that JAXB 2.0 jar files appear on the classpath before JAXB 1.0 jar file (xml.jar).

MDS-01358
Invalid MDS configuration. Configuring multiple metadata stores as the default repository for customizations.

Category:
Configuration

Cause:
Multiple metadata stores were configured as the default repository for customizations in the MDS configuration.

Action:
Ensure that only a single metadata store is configured as the default repository for customizations.

MDS-01359
The namespace used (http://xmlns.oracle.com/mds/config_10_1_3_001) in the configuration document is deprecated. Update the configuration document to use "http://xmlns.oracle.com/mds/config" as the namespace.

Category:
Configuration

Cause:
The namespace used (http://xmlns.oracle.com/mds/config_10_1_3_001) in the configuration document is deprecated.

Action:
Update the configuration document to use "http://xmlns.oracle.com/mds/config" as the namespace.

MDS-01360
Invalid MDS configuration. The attribute file-type-extension on the file-type element is missing for file type configuration.

Category:
Configuration

Cause:
The attribute file-type-extension was not specified on the file-type element for file type configuration.

Action:
Ensure that a valid file-type-extension attribute is specified for every file-type element.

MDS-01361
cannot add XSD grammar

Category:
Configuration

Cause:
An attempt was made to add XSD grammar made by passing in a SchemaGrammarProvider.

Action:
Ensure that the grammar provider is obtained using oracle.jdeveloper.webapp.runtime.WebAppDesignContext.

MDS-01362
Failed to auto-purge MDS repository: "{0}".

Category:
Other

Cause:
MetadataStore was scheduled for auto-purge after the MDSInstance was released

Action:
Try later and contact support if persists.

MDS-01363
Failed to lookup datasource with JNDI name "{0}" configured for the DBMetadataStore, defaulting to use ClassPathMetadataStore.

Category:
Configuration

Cause:
Application was configured with DBMetadataStore using JNDI datasource and JNDI lookup failed when running outside application server.

Action:
No action required if defaulting to ClasspathMetadataStore is acceptable. Otherwise, use appropriate configuration such as FileMetadataStore.

MDS-01364
Namespace mapping for "{0}" is overlapping with namespace mapping for "{1}"; the first mapping is redundant.

Category:
Configuration

Cause:
Redundant namespace mappings defined in the persistence configuration.

Action:
Correct persistence configuration to ensure that there is no overlapping redundant mapping.

MDS-01365
Multiple metadata stores found with deploy-target attribute set to true, only one allowed per configuration.

Category:
Configuration

Cause:
Multiple metadata stores were configured as the deployment target.

Action:
Ensure that only a single metadata store is configured for deployment.

MDS-01366
Cannot find a metadata store with deploy-target attribute set to true

Category:
Configuration

Cause:
A single metadata store must be configured as a deploy target. None was found.

Action:
Ensure that a single metadata store is configured for deployment.

MDS-01367
Failed to create {0}. Invalid MDS configuration specified in: "{1}"

Category:
Configuration

Cause:
Declarative MDS configuration is invalid.

Action:
Specify correct mds configuration information and try creating the configuration again.

MDS-01368
Variable "{0}" used in configuration document is not defined either as system property or as environment variable.

Category:
Configuration

Cause:
This variable was not defined.

Action:
Ensure that this variable is defined before loading the configuration.

MDS-01369
Variable declaration in "{0}" in configuration document is incorrect.

Category:
Configuration

Cause:
Variable did not either start with "${" or it did not end with "}".

Action:
Ensure that the configuration variable is correctly declared in the form ${var}.

MDS-01370
MetadataStore configuration for metadata-store-usage "{0}" is invalid.

Category:
Configuration

Cause:
MetadataStore class or some of its properties were not valid.

Action:
Ensure that the MetadataStore class exists and all required properties are valid. See message of the cause exception for more information on the actual reason for failure.

MDS-01371
ADF security is not configured in "{0}", password cannot be securely processed.

Category:
Configuration

Cause:
ADF security configuration was not found in the config file.

Action:
Set the password using JDeveloper to ensure required configuration is generated.

MDS-01373
unable to retrieve password.

Category:
Configuration

Cause:
unable to retrieve the password due to exception in security layer.

Action:
See message of the cause exception for more information on the actual reason for failure.

MDS-01374
unable to save password.

Category:
Configuration

Cause:
unable to save the password due to exception in security layer.

Action:
See message of the cause exception for more information on the actual reason for failure.

MDS-01375
No password defined for DBMetadataStore in configuration file or in the wallet file.

Category:
Configuration

Cause:
DBMetadataStore uses JDBC based configuration but no password specified.

Action:
Set the password for the DBMetadataStore using JDeveloper.

MDS-01376
Unable to get database connection from data source "{1}" configured with JNDI name "{0}".

Category:
Configuration

Cause:
Failed to retrieve a database connection from the data source either because the data source is not configured correctly or the database details are not correct.

Action:
Test the data source to check if it is correctly configured and if the database can be accessed. See message of the cause exception for more information on the actual reason for failure.

MDS-01377
Unable to get database connection from data source configured with JNDI name "{0}".

Category:
Configuration

Cause:
Failed to retrieve a database connection from the data source either because the data source is not configured correctly or the database details are not correct.

Action:
Test the data source to check if it is correctly configured and if the database can be accessed. See message of the cause exception for more information on the actual reason for failure.

MDS-01378
metadata-store-usage attribute should not be set on namespace "{0}" defined in mds-config.xml.

Category:
Configuration

Cause:
metadata-store-usage attribute was set on the specified namespace in mds-component-config, but this namespace is always assumed to map to deploy-target metadata store.

Action:
Ensure that the metadata-store-usage attribute is removed on specified namespace in mds-config.xml.

MDS-01379
Tenant scope "{0}" is not valid for namespace "{1}" with namespace restriction "{2}".

Category:
Configuration

Cause:
Tenant scope configured for the namespace is not supported with the configured namespace restriction.

Action:
Resolve the conflict between tenant scope and namespace-restriction in the application configuration.

MDS-01380
Tenant scoped base metadata in package "{0}" can not have global customization layer "{1}".

Category:
Configuration

Cause:
Tenant scope GLOBAL on the specified customization layer conflicts with tenant scope TENANT on the base namespace.

Action:
Resolve the conflicts between the tenant scope on the base namespace and that on the customization layer.

MDS-01381
Customization layer "{0}" has been configured more than once with the same tenant scope.

Category:
Configuration

Cause:
Duplicate configuration for the same customization layer was found.

Action:
Remove the duplicate customization layer configuration from adf-config.xml of the application or component config (mds-config.xml) on classpath.

MDS-01382
Customization layer "{0}" has been configured more than once with conflicting tenant scopes.

Category:
Configuration

Cause:
Conflicting tenant scope configurations was found for the same customization layer.

Action:
Remove the incorrect customization layer configuration from adf-config.xml of the application or component config (mds-config.xml) on classpath.

MDS-01383
Sandbox name should be provided for registering a sandbox change listener.

Category:
Configuration

Cause:
No sandbox name was provided for registering the sandbox change listener.

Action:
Provide a valid sandbox name when registering the sandbox change listener.

MDS-01384
Sandbox change listener is not found when registering the lifecycle listener for sandbox {0}.

Category:
Configuration

Cause:
The SendboxChangeListener being registered was null.

Action:
Provide a valid sandbox change listener when registering the lifecycle listener for the sandbox.

MDS-01385
Tenant scope "{0}" as base tenant scope is not valid for namespace "{1}".

Category:
Configuration

Cause:
The specified tenant scope type could not be configured as base tenant scope for the namespace.

Action:
Use the correct base tenant scope parameter to create the namespace.

MDS-01386
Multitenant application can not be configured with metadata store "{0}" that does not support multitenancy.

Category:
Configuration

Cause:
A metadata store that does not support multitenancy was configured for a multitenant enabled application.

Action:
Configure a metadata store such as DBMetadataStore that supports multitenancy.

MDS-01387
Tenant with id "{0}" is not allowed to change the autopurge settings; only the global admin can change this configuration.

Category:
Configuration

Cause:
A tenant cannot change the autopurge configuration..

Action:
Only a global admin can change the autopurge configuration.

MDS-01388
Unable to set cache size to {0} KiloBytes.

Category:
Programmatic

Cause:
The cache size requested was invalid either because it was negative or it was too large for the Java Object Cache.

Action:
Check that the specified size is >0 and within the limit for the cache implementation.

MDS-01389
content-type cannot be specified for content-config mapping [File extension={0}, Path to match={1}] since isStreamed is set to true.

Category:
Configuration

Cause:
Conflicting settings between content-type and isStreamed were found in content-config.

Action:
Change content-options to use content-type without causing conflict.

MDS-01390
An audit event name for component "{0}" is not specified.

Category:
Configuration

Cause:
An audit event was defined, but a name for the event was not specified.

Action:
Give the audit event a valid name.

MDS-01391
"{0}" is not a valid audit event name.

Category:
Configuration

Cause:
An invalid audit event name was found. An audit event name should start with a letter and contain only letters and digits.

Action:
Specify a valid name for the audit event.

MDS-01392
Conflicting definitions were found for the audit event with name "{0}" and audit-component "{1}".

Category:
Configuration

Cause:
Conflicting audit event definitions were found in audit-component element.

Action:
Remove or modify one of the conflicting audit events.

MDS-01393
Multiple audit events named "{0}" are defined for component "{1}".

Category:
Configuration

Cause:
Duplicate audit events were found in audit-component element.

Action:
Remove or modify one of the duplicate audit events.

MDS-01394
The repository-name property element is not specified for a metadata-store element that does not have the class-name property.

Category:
Configuration

Cause:
The repository-name property element was not specified for a metadata-store element. It is required when the class-name property is not specified on the metadata-store element to support look up of the repository details.

Action:
Specify the repository name in a child property element of the metadata-store element or specify the class-name property for the metadata-store element in the configuration file.

MDS-01395
Unable to look up the details of the specified repository {0} for the metadata-store configuration.

Category:
Configuration

Cause:
The specified repository was not registered in the domain or the repository was not configured properly.

Action:
Ensure that the specified repository for the metadata-store is configured and registered properly in the domain.

MDS-01396
metadata-store-usage attribute is not set on namespace "{0}" defined in mds-config.xml.

Category:
Configuration

Cause:
metadata-store-usage attribute was missing on the specified namespace in mds-component-config.

Action:
Ensure that the metadata-store-usage attribute is set on the specified namespace in mds-config.xml.

MDS-01397
Multiple audit events with display name "{0}" are defined for component "{1}".

Category:
Configuration

Cause:
More than one audit event was found with the same display name in audit-component element.

Action:
Ensure that the display names are unique for all audit events of a component.

MDS-01398
Namespace "{0}" is mapped to both metadata store "{1}" and metadata store "{2}".

Category:
Configuration

Cause:
There were multiple metadata stores mapped to a given namespace in the persistence configuration.

Action:
Correct the namespace mapping in persistence configuration to ensure that the namespace is mapped to only one metadata store.

MDS-01399
A DBMetadataStore store is being registered with a PManager with multitenant enabled set to {1} but an equal store is already registered with a PManager with multitenant enabled set to {0}.

Category:
Configuration

Cause:
The DBMetadataStore store being registered cannot be used for both multitenant and non multitenant operations at the same time.

Action:
Ensure that the same physical store is not used for both multitenant and non multitenant operations.

MDS-01400
Read-only extended metadata resource "{0}" is not writable.

Category:
Programmatic

Cause:
An attempt was made to update a read-only extended metadata resource.

Action:
Ensure that the metadata object is mutable before getting the extended metadata.

MDS-01401
Updating a node in one document "{1}" using a node from a different document "{0}" is not allowed.

Category:
Programmatic

Cause:
The node being added or inserted was from a different metadata object. They must be from the same base document.

Action:
Ensure that the node being inserted is from the correct metadata object.

MDS-01402
Updating immutable MetadataObject "{0}" is not allowed.

Category:
Programmatic

Cause:
The MetadataObject being updated was immutable.

Action:
Ensure that the MetadataObject to be updated is mutable.

MDS-01403
Updating a mutable MElement in MetadataObject "{0}" using an immutable MElement: "{1}" is not allowed.

Category:
Programmatic

Cause:
An attempt was made to update a mutable MElement using an immutable MElement.

Action:
Verify that the child MElement being used for the update is mutable.

MDS-01404
Customization to replace root node of {0} is not allowed.

Category:
Programmatic

Cause:
An attempt was made to replace the root node as part of a customization.

Action:
Replace the root node in the base document, or modify the existing root node instead.

MDS-01450
missing GUID

Category:
Programmatic

Cause:
The application removed an object's GUID while editing its XML metadata content.

Action:
Fix the application so it does not tamper with MDS GUIDs.

MDS-01451
GUIDs do not match.

Category:
Programmatic

Cause:
The application altered an object's GUID while editing its XML metadata content.

Action:
Fix the application so it does not tamper with MDS GUIDs.

MDS-01452
GUID is null.

Category:
Programmatic

Cause:
An attempt was made to retrieve a metadata object or document by GUID, but the given GUID was null.

Action:
Fix the application so it passes a valid GUID to the method in question.

MDS-01455
multiple GUIDs on metadata object {0}

Category:
Programmatic

Cause:
The application set multiple GUID values while editing an object's XML metadata content.

Action:
Fix the application so it does not tamper with MDS GUIDs.

MDS-01456
invalid GUID on metadata object {0}

Category:
Programmatic

Cause:
The application set an object's GUID to an invalid value while editing its XML metadata content.

Action:
Fix the application so it does not tamper with MDS GUIDs.

MDS-01457
GUID feature not available

Category:
Programmatic

Cause:
The application attempted to retrieve an object by GUID from a metadata store that does not yet support this.

Action:
Fix the application so it does not attempt this, or configure the application to use a different type of metadata store.

MDS-01458
GUID must not be present.

Category:
Programmatic

Cause:
The application set an object's GUID value while editing its XML metadata content.

Action:
Fix the application so it does not tamper with MDS GUIDs.

MDS-01460
GUIDs on DOM Document do not match.

Category:
Programmatic

Cause:
The application set an object's GUID to a different value while editing its XML metadata content.

Action:
Fix the application so it does not tamper with MDS GUIDs.

MDS-01461
unable to create document {0} in the metadata repository; a document with the same name or GUID already exists

Category:
Data

Cause:
An attempt was made to import or create a document with a name or GUID that is already used by an existing document.

Action:
Delete the document in the MDS repository prior to import or creation.

MDS-01462
GUID feature is not supported in the classpath store.

Category:
Programmatic

Cause:
The application attempted to retrieve an object by GUID from the classpath metadata store that does not support this.

Action:
Fix the application so it does not attempt retrieval by GUID, or configure the application to use a different type of metadata store.

MDS-01464
unable to save GUIDRegister {0}

Category:
Files

Cause:
The GUID register (GUID index files) could not be written.

Action:
Verify that the application has write permission for the given file, and that the disk is not full.

MDS-01465
unable to remove node {0} from the GUIDRegister

Category:
Data

Cause:
The given node was not removed from the GUID register, possibly because it was not found.

Action:
Delete the GUID register files, restart the application and try the operation again. If that fails, contact Oracle Support Services.

MDS-01466
unable to create GUIDRegister directory {0}

Category:
Files

Cause:
The owning directories for the GUID register (GUID index files) were not created.

Action:
Verify that you have permission to create the parent directories for the given file name.

MDS-01468
A different GUID is already registered for document {0}.

Category:
Data

Cause:
The GUID register has become corrupted.

Action:
Delete the GUID register files and restart the application (the files will then be re-created).

MDS-01469
unable to remove old GUIDRegister store path {0}

Category:
Files

Cause:
Old GUID register files were not deleted.

Action:
Verify that you have permission to delete these files.

MDS-01470
more than one GUID is registered for document {0}

Category:
Data

Cause:
The GUID register has become corrupted.

Action:
Delete the GUID register files and restart the application (the files will then be re-created).

MDS-01471
more than one document is registered for GUID {0}

Category:
Data

Cause:
The GUID register has become corrupted.

Action:
Delete the GUID register files and restart the application (the files will then be re-created).

MDS-01472
GUID is missing in file {0}

Category:
Data

Cause:
No GUID was found in the given file but the metadata object type definition indicated there should be one.

Action:
Re-create the metadata object or correct its type definition not to require a GUID.

MDS-01500
The MDSObject {0} is an XML document and cannot be loaded using StreamedObject API.

Category:
Programmatic

Cause:
An attempt was made to load an XML document via StreamedObject API.

Action:
Retry the operation using MetadataObject API or use a non-XML document.

MDS-01501
The MDSObject {0} is not an XML document and cannot be loaded from MetadataObject API.

Category:
Programmatic

Cause:
An attempt was made to load a streamed object (non-XML document) using MetadataObject API.

Action:
Retry the operation using StreamedObject API or use a document containing valid XML.

MDS-01502
The MDSObject "{0}" is an XML document and cannot be saved using StreamedObject API.

Category:
Programmatic

Cause:
An attempt was made to save an XML document using StreamedObject API.

Action:
Retry the operation using MetadataObject API.

MDS-01503
The content of StreamedObject {0} cannot be read.

Category:
Data

Cause:
An attempt to read the StreamedObject content failed.

Action:
Look at the error message and exception stack in the application logs to determine the reason for the failure.

MDS-01504
The document {0} is either registered as a streamed file type or is a non-XML file extension and cannot be created using MetadataObject API.

Category:
Programmatic

Cause:
An attempt was made to create an MDSObject named with a streamed object (non-XML) extension using MetadataObject API.

Action:
Retry the operation using StreamedObject API.

MDS-01600
The Dependency Analyzer requires a DependencyFilter.

Category:
Programmatic

Cause:
Either no filter was supplied, or the filter supplied was null.

Action:
Supply a non-null filter.

MDS-01601
The relationship role name {0} is a duplicate.

Category:
Programmatic

Cause:
A role name defined in a relationship had already been used.

Action:
Ensure that the toParentRole and toChildRole in a relationship have not already been used by another relationship.

MDS-01602
cannot locate the element type {0} in namespace {1} defined for the relationship

Category:
Programmatic

Cause:
The element type did not exist in the given namespace.

Action:
Ensure that the element type exists in the given namespace.

MDS-01604
The relationship from {0} to {1} is invalid because the latter is not a valid MDS reference.

Category:
Programmatic

Cause:
An invalid MDS reference was specified as the parent.

Action:
Ensure the parent reference is a valid MDS reference.

MDS-01605
The relationship from {0} to {1} is invalid because the latter does not exist.

Category:
Programmatic

Cause:
No parent element was found matching the MDS reference supplied.

Action:
Ensure that the parent reference in the relationship points to an existing element.

MDS-01606
The relationship from {0} to {1} is invalid because the latter is of incorrect type.

Category:
Programmatic

Cause:
The child element referenced a parent of the wrong type.

Action:
Ensure that the parent type matches the one stipulated in the relationship definition.

MDS-01607
The relationship from {0} to {1} is invalid because type information is not available for the latter.

Category:
Configuration

Cause:
No type definition could be found for the parent.

Action:
Ensure that the parent type information is available.

MDS-01608
The relationship from {0} to {1} is invalid because the latter maps to a different store.

Category:
Configuration

Cause:
The parent and child objects in the relationship have been mapped to different stores.

Action:
Ensure that the parent maps to the same store as the child object.

MDS-01609
The document {0} contains relationships that do not conform to the relationship definition.

Category:
Programmatic

Cause:
Constraints in this document's relationship definitions were violated.

Action:
Ensure that the relationships conform to the constraints in the relationship definition.

MDS-01610
Some of the changes in the MDS session are not valid.

Category:
Data

Cause:
A change was made in the MDS session that was not valid.

Action:
Check the changes made and ensure each of them is valid.

MDS-01611
not saving changes in MDS session because some changes are not valid

Category:
Data

Cause:
A change made in the MDS session was not valid.

Action:
Check all the changes made and ensure that all changes are valid.

MDS-01612
The object {0} cannot be deleted because it is referenced by {1}.

Category:
Programmatic

Cause:
An attempt was made to delete an element that was being referenced by a child object.

Action:
Remove the child reference to this object so the object can be deleted.

MDS-01613
The object {0} cannot be deleted because of relationship integrity constraints.

Category:
Programmatic

Cause:
An attempt was made to delete an object that was still being referenced.

Action:
Remove the child references to the metadataObject so that it can be deleted.

MDS-01614
Rename is not allowed because integrity checking is not turned on in the object {1} in MetadataObject {0}.

Category:
Configuration

Cause:
Integrity checking was switched off so it was not possible to check whether the rename would have broken any relationship integrity constraints.

Action:
Ensure that integrity checking is turned on.

MDS-01615
failure to rename {0} because there is no reference attribute in MetadataObject {1}, element {2}

Category:
Data

Cause:
A child object could not reference the renamed object as its current reference was invalid.

Action:
Confirm that all the references in the child object are valid.

MDS-01620
The untyped dependency with the following registration details cannot be inserted: {0}, {1}, {2}, {3}.

Category:
Data

Cause:
The dependency could not be registered in the database repository due to a SQL exception.

Action:
Correct the cause of the SQL exception and retry the untyped dependency registration.

MDS-01621
The untyped dependency information for {0} could not be removed.

Category:
Data

Cause:
An attempt to remove untyped dependency information failed either because the document was invalid or there was a SQL exception.

Action:
Verify that the document and its dependencies are valid, or correct the cause of any SQL exceptions.

MDS-01622
There is no analyzer to unregister.

Category:
Configuration

Cause:
No analyzers were supplied to be unregistered.

Action:
Supply the DependencyAnalyzer to be unregistered.

MDS-01630
invalid operation in a customized context on an element that could participate in a relationship: {0}

Category:
Programmatic

Cause:
Within a customized context there was an attempt to insert an element without first deleting it as part of a composite move.

Action:
Within the customized context, do not attempt inserts on elements without first deleting them as part of a composite move.

MDS-01631
In a customized context, an element that could participate in a relationship as a child cannot be modified. The reference is {0} on {1}.

Category:
Programmatic

Cause:
Within a customized context, an attribute being customized could have been a parent reference within a relationship.

Action:
Do not attempt to modify or remove an attribute that could be a parent reference within a relationship.

MDS-01633
In a customized context, an element that could participate in a relationship cannot be deleted: {0}.

Category:
Programmatic

Cause:
Within a customized context an attempt was made to delete an element that could participate in a relationship.

Action:
Do not attempt to delete an entity while in a customized context.

MDS-01634
In {0}, a {1} element that participates in a relationship lacks a configurable ID.

Category:
Programmatic

Cause:
An operation was attempted on a participant in a relationship that lacked a configurable ID.

Action:
Add a configurable ID to the element on which it is missing. If necessary, refer to the element's schema definition to identify the configurable ID attribute.

MDS-01635
Skipping the relationship validation for {0} in the metadata object {1} because the element contains an invalid MDS reference.

Category:
Programmatic

Cause:
Validation of the object's relationships was not performed because the element contained an invalid MDS reference.

Action:
Correct the MDS references in the MetadataObject specified.

MDS-01700
MElementBeanImpl._setSimpleChild cannot be called on a non-simpleType element: name={0}, namespace{1}

Category:
Configuration

Cause:
An attempt was made to set a bean element to a simple type, but the definition in the schema was not a simple type. The generated beans may not have matched the registered schema.

Action:
Regenerate the beans from the schema definitions and ensure that the correct versions are on the classpath. Check that the schemas are registered with the MDS instance.

MDS-01701
Cannot set the value on an element that is not based on a simpleType: name={0}, namespace={1}

Category:
Configuration

Cause:
An attempt was made to set an element to a simple type, but the definition in the schema was not a simple type.

Action:
Regenerate the beans from the schema definitions and ensure that the correct versions are on the classpath. Check that the schemas are registered with the MDS instance.

MDS-01702
The method getBean() is not valid for metadata object {0} - it is allowed on only bean metadata objects.

Category:
Configuration

Cause:
An attempt was made to access the metadata object using the bean API but the metadata object was not a bean metadata object. The schema for the root element may not have been registered with MDS, or the beans were not available on the classpath.

Action:
Regenerate the beans from the schema definitions and ensure that the correct versions are on the classpath. Check that the schemas are registered with the MDS instance.

MDS-01703
error unmarshalling bean element: name={0}, namespace={1} in metadata object {2} - no object factory can be found or jaxb.properties cannot be found

Category:
Configuration

Cause:
An element was found in the metadata object that did not have a corresponding bean class. The schema for the element may not have been registered with MDS, or the beans were not available on the classpath.

Action:
Regenerate the beans from the schema definitions and ensure that the correct versions are on the classpath. Check that the schemas are registered with the MDS instance.

MDS-01705
error unmarshalling bean element: name={0}, namespace={1} in metadata object {2} - object factory class {3} does not have the expected unmarshal() method

Category:
Data

Cause:
The bean object factory found for the element did not appear to have been generated by the MDS bean generation tool.

Action:
Regenerate the beans from the schema definitions and ensure that the correct versions are on the classpath. Check that the schemas are registered with the MDS instance.

MDS-01706
error unmarshalling bean element: name={0}, namespace={1} in metadata object {2} - object factory class {3} failure in unmarshal() method

Category:
Programmatic

Cause:
An unexpected exception occurred while creating a bean object for the element.

Action:
Contact the developers of the application, providing the cause exception.

MDS-01707
Error generating relationship method {0} for relationship defined on attribute {1}: incorrect parentType definition

Category:
Programmatic

Cause:
There was an error in the relationship definition.

Action:
Check the parentType definition on the relationship

MDS-01708
No schema definition found in namespace "{0}" for element of type "{1}". {2} will not be retrievable as an MDS Bean MO.

Category:
Configuration

Cause:
The schema for the generated MDS bean is not found.

Action:
Add the schema for this namespace and element type to the type definitions for the MDSInstance.

MDS-01800
Sandbox is not supported for {0} configured on {1}.

Category:
Configuration

Cause:
An underlying metadata store did not support the sandbox feature.

Action:
Provide a metadata store that supports sandbox feature.

MDS-01801
Document name {0} should not refer to the raw sandbox resource name.

Category:
Programmatic

Cause:
A resource name pointed directly to a resource in the sandbox component.

Action:
Provide a logical document name to resolve the issue.

MDS-01802
A sandbox by name {0} already exists in the {1} store.

Category:
Configuration

Cause:
A sandbox with the same name already existed in the store.

Action:
Use a different name or destroy the existing sandbox before reusing the same name.

MDS-01803
Sandbox Persistence manager cannot be constructed using an instance of SandboxPManager.

Category:
Programmatic

Cause:
An attempt was made to construct an instance of sandbox persistence manager using an instance of SandboxPManager.

Action:
Contact Oracle Support Services.

MDS-01804
Sandbox {0} configured with {1} namespace, {2} store and {3} label from mainline is not compatible with {4} label created on {5} namespace.

Category:
Programmatic

Cause:
A label was used that is different from the mainline label associated with the sandbox.

Action:
Use a label that is compatible with the sandbox and retry the operation.

MDS-01805
Sandbox {0} missing in {1}.

Category:
Data

Cause:
The specified sandbox was not found in the underlying metadata store.

Action:
Provide the name of an existing sandbox, or create a new sandbox if necessary.

MDS-01806
failure to remove {0} from {1}, because it is not a valid document in the sandbox

Category:
Data

Cause:
The specified document to be removed was not found in the sandbox.

Action:
Verify that the document exists in the sandbox.

MDS-01807
failure to delete sandbox {0}

Category:
Programmatic

Cause:
An error occurred while deleting the sandbox.

Action:
Refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-01808
SandboxUsage with the sandbox name set to {0} does not return any namespaces.

Category:
Programmatic

Cause:
No namespaces were found on the SandboxUsage.

Action:
Configure the SandboxUsage with namespaces that are associated with the sandbox.

MDS-01809
failure to list sandboxes matching {0}

Category:
Programmatic

Cause:
An error occurred while listing or querying the sandboxes.

Action:
Look for error messages to determine the actual cause of the failure.

MDS-01810
failure to refresh sandboxes to target label {0}

Category:
Programmatic

Cause:
Target label is older than the current source label.

Action:
Specify a target label which is later than current label.

MDS-01811
failure to list sandboxes matching customization for {0}, layer: {1}, value: {2}

Category:
Programmatic

Cause:
An error occurred while listing or querying the sandboxes.

Action:
Look for error messages to determine the actual cause of the failure.

MDS-01812
sandbox name {0} exceeds the maximum limit of {1} characters

Category:
Programmatic

Cause:
Sandbox name is more than the supported size.

Action:
Use a shorter sandbox name.

MDS-01813
sandbox metadata for {0} cannot be saved because it is being updated by another user.

Category:
Programmatic

Cause:
More than one user is updating the sandbox metadata at the same time.

Action:
Get the sandbox metadata again and retry saving after making the changes.

MDS-01814
sandbox metadata for {0} cannot be changed because it is read only.

Category:
Programmatic

Cause:
Sandbox metadata is read only and cannot be updated

Action:
To update get an instance of sandbox and then get the sandbox metadata from the instance

MDS-01815
store configured for sandbox {0} does not support sandbox metadata.

Category:
Programmatic

Cause:
Sandbox metadata is not supported on the repository.

Action:
Sandbox metadata is supported in MDS repository version 11.1.1.4.0 (11gR1 PS3 patchset) onwards. Upgrade the repository to this version or later to use this feature.

MDS-01816
{0} is not a valid name for a sandbox.

Category:
Programmatic

Cause:
The specified sandbox name is either an MDS reserved package part name or contains invalid characters.

Action:
Ensure that the specified sandbox name is neither an MDS reserved package part name nor does it contain invalid characters as per the MDS Resource name specification.

MDS-01817
sandbox {0} is either active or published to mainline. The undo/finalize operation cannot continue.

Category:
Programmatic

Cause:
The sandbox is either applied or is in the active state.

Action:
Check that the sandbox is in the intermediary state

MDS-01818
sandbox {0} is either being refreshed or applied and is in intermediary state. No further updates except sandbox finalize/undo operation are allowed.

Category:
Programmatic

Cause:
The sandbox is in intermediary state and no further updates can be done to the sandbox.

Action:
The only allowed operations in the intermediary state are: finalize and undo.

MDS-01819
Lock on sandbox {0} cannot be taken. A concurrent management operation may be in progress.

Category:
Programmatic

Cause:
A management operation on the sandbox is in progress and has locked the sandbox.

Action:
Retry the operation after a while.

MDS-01820
Metadata for sandbox {0} is not available. The sandbox management operation cannot proceed without sandbox metadata.

Category:
Programmatic

Cause:
Sandbox was created without metadata.

Action:
Use the management APIs that are available for sandboxes without metadata.

MDS-01821
Lifecycle change notifications for the sandbox {0} cannot be sent out because the change type is not defined.

Category:
Other

Cause:
The sandbox lifecycle change does not have a valid change type.

Action:
Contact Oracle Support Services.

MDS-01900
None of the configured metadata stores support versioning.

Category:
Configuration

Cause:
The underlying metadata store did not support versioning.

Action:
Configure a metadata store that supports versioning, and retry the operation.

MDS-01901
specifying multiple labels for a namespace not allowed

Category:
Configuration

Cause:
Multiple labels were provided for a namespace that pointed to a metadata store.

Action:
Provide a single label to map to a namespace and retry the operation.

MDS-01902
Label or namespace is invalid.

Category:
Programmatic

Cause:
Either the namespace or the label was invalid.

Action:
Verify that the namespace and the label are correct, and retry the operation.

MDS-01903
Specified label {0} does not exist for {1} namespace.

Category:
Configuration

Cause:
The specified label did not exist in the metadata store mapped to the namespace.

Action:
Verify that the label name is correct and that the label exists, and then retry the operation.

MDS-01906
A label with same name {0} already exists.

Category:
Programmatic

Cause:
An attempt was made to create a label that already existed.

Action:
Create a label with a different name, and then retry the operation.

MDS-01907
The label {1} is already configured for the store "{0}", so the same store cannot be configured with another label "{2}".

Category:
Configuration

Cause:
An attempt was made to map a label for a store when a label-to-store mapping already existed for that store.

Action:
De-associate the existing label mapped to the store first, and then retry the operation.

MDS-01908
failure to delete versions of the document {0}

Category:
Programmatic

Cause:
An error had occurred while versions were being deleted.

Action:
Refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-01909
No namespaces are specified for creating label {0}.

Category:
Programmatic

Cause:
No namespace information was found for creating a label.

Action:
Provide a namespace for creating a label, and retry the operation.

MDS-01910
The namespace {0} is already registered with the label {1}, so the super/sub namespace {2} cannot be assigned with the label {3}.

Category:
Programmatic

Cause:
An attempt was made to associate multiple labels with a namespace, or an attempt was made to associate multiple namespaces with a single label.

Action:
Associate a single label with a single namespace, and retry the operation.

MDS-01911
failure of the metadata purge operation for the requested repository partition

Category:
Programmatic

Cause:
An error occurred during a purge operation.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-01912
MetadataStore configured for {0} does not support versioning.

Category:
Configuration

Cause:
The metadata store configured for the resource did not support versioning.

Action:
Configure a metadata store that supports versioning or verify that the resource name is correct.

MDS-01913
A deployment lineage with same application name "{0}" and deployment module name "{1}" already exists.

Category:
Programmatic

Cause:
An attempt was made to create a lineage that already existed.

Action:
Create a lineage with a different application or MAR name, and then retry the operation.

MDS-01914
The application name and deployment module name cannot be null to create DeploymentInfo.

Category:
Programmatic

Cause:
An attempt was made to create DeploymentInfo with null values.

Action:
Make sure that the values for application name and deployment module name are non-null.

MDS-02001
Absolute path as metadata-path for the file metadata-store configuration is not supported for SaaS deployment.

Category:
Configuration

Cause:
Configuring an absolute directory in SaaS Multitenant application will violate metadata isolation across tenants.

Action:
Ensure that relative path specified as metadata-path for the file metadata-store.

MDS-02002
RelativeToLocation for the file metadata-store configuration is not supported for SaaS deployment.

Category:
Configuration

Cause:
Configuring an absolute directory in SaaS Multitenant application will violate metadata isolation across tenants.

Action:
Ensure that relative path is specified as metadata-path for the Metadata Store and RelativeToLocation is null

MDS-02003
Package name {0} in cust-restriction-config in {1} is invalid.

Category:
Configuration

Cause:
An invalid package name was encountered whilst loading the component configuration.

Action:
Ensure that a valid package name is specified

MDS-02004
Cannot configure [Path to match={0}] as Layered Stream Objects since path's content-type is not BINARY_STREAM.

Category:
Configuration

Cause:
customization-type attribute in cust-config can be set to FULL_REPLACE only when content-config configures the path as BINARY_STREAM.

Action:
Change content-type to use BINARY_STREAM or remove customization-type configuration.

MDS-02005
Cannot configure [Path to match={0}] as Layered Stream Objects since path is configured for stream storage in content-config using isStreamed option.

Category:
Configuration

Cause:
cust-type is not supported with isStreamed as isStreamed attribute is deprecated.

Action:
Remove isStreamed and configure content-type to use BINARY_STREAM or remove cust-type configuration.

MDS-02006
streamBuilder class not specified for path {0}.

Category:
Configuration

Cause:
The streamBuilder class cannot be null if customization-type is configured as 'extension'.

Action:
Ensure that the streamBuilder class is supplied when configuring customization-type as 'extension'.

MDS-02007
streamBuilder can only be specified with customization-type 'extension' for path {0}.

Category:
Configuration

Cause:
streamBuilder is only valid for 'extension' customization-type.

Action:
Ensure that the streamBuilder class is only supplied when configuring customization-type as 'extension'.

MDS-02024
Setting or modifying the unique (or locally unique) identifier "{0}" of an existing element with localRef "{1}" through customizations is not supported.

Category:
Programmatic

Cause:
An attempt was made to customize unique (or locally unique) identifier.

Action:
Remove any customization that is attempting to modify the unique (or locally unique) identifier of an XML element.

MDS-02025
The requested change is incompatible with changes already pending on the MDS session.

Category:
Programmatic

Cause:
An attempt was made to perform a change operation on the MDS session which would update the same MetadataObject part as another change operation that has been done. For example, if you change a customization of a metadata object then attempt to delete all of its customizations, the latter operation will fail because it conflicts with the former. You must save the former change first before doing the second.

Action:
Save the changes that have already been made on the session (by calling flushChanges), then retry the failed operation.

MDS-02100
Illegal permission target: "{0}" - must begin with {1}.

Category:
Programmatic

Cause:
An attempt was made to create an MDS permission class with an incorrect syntax.

Action:
Permission classes are usually created internally by MDS but may be created by the application directly. Contact the developers of the application to confirm that this is not an application error and if not contact Oracle Support Services.

MDS-02101
Illegal permission action: "{0}" - unknown action.

Category:
Programmatic

Cause:
An attempt was made to create an MDS permission class with an incorrect syntax.

Action:
Permission classes are usually created internally by MDS but may be created by the application directly. Contact the developers of the application to confirm that this is not an application error and if not contact Oracle Support Services.

MDS-02102
Illegal permission action: "{0}" - customize action takes 0 or 2 parameters.

Category:
Programmatic

Cause:
An attempt was made to create an MDS permission class with an incorrect syntax.

Action:
Permission classes are usually created internally by MDS but may be created by the application directly. Contact the developers of the application to confirm that this is not an application error and if not contact Oracle Support Services.

MDS-02201
type validation failure for the metadata object "{0}"

Category:
Programmatic

Cause:
The content of the metadata object was not valid against the registered XSDs.

Action:
Ensure that the metadata object content is valid with respect to the registered XSDs.

MDS-02202
Content of the metadata object "{0}" is not valid.

Category:
Programmatic

Cause:
The content was not valid either with respect to the registered XSDs or with the registered relationships.

Action:
Check the content of the metadata object and correct the content as necessary to make it valid.

MDS-02203
type validation error for the metadata object "{0}" at the node "{1}": {2}

Category:
Programmatic

Cause:
A validation error occurred at the specified node.

Action:
Check the content at the specified node for compliance with registered XSDs and relationships.

MDS-02204
type validation warning for the metadata object "{0}" at the node "{1}": {2}

Category:
Programmatic

Cause:
A validation warning occurred at the specified node.

Action:
Check the content at the specified node for compliance with registered XSDs.

MDS-02301
The rename unit is invalid because either "{0}" or "{1}" is reused in the rename plan.

Category:
Programmatic

Cause:
The resource name provided in the rename plan was used more than once.

Action:
Provide distinct names for source and target names while renaming.

MDS-02302
subobjects "{1}" not found in metadata object "{0}"

Category:
Programmatic

Cause:
The specified subobjects were not found in the metadata object.

Action:
Look in the error message log for details.

MDS-02303
The given rename plan syntax is invalid

Category:
Configuration

Cause:
The rename plan syntax specified was invalid.

Action:
Look in the error message log for details.

MDS-02304
RenameOperation failed for StreamedObject "{0}" because subobjects were specified for this streamed object.

Category:
Programmatic

Cause:
Streamed objects do not support subobjects.

Action:
Remove the RenameObject that contains reference to the streamed object and subobject references from the RenamPlan.

MDS-02401
The operation {0} on the {1} node is not allowed.

Category:
Configuration

Cause:
An attempt was made to customize a node that was not customizable.

Action:
If the attempted customization is valid, the customization restrictions need to be modified to provide this ability. The customization restrictions can be defined in: the XML schema definition, standalone XML file or an extended metadata file. Also check the customization policy for the MDS session in use and the customization configuration.

MDS-02402
The type definition for {1} does not allow customization of {0}.

Category:
Configuration

Cause:
An attempt was made to customize a node that was not customizable.

Action:
If the attempted customization is valid, the customization restrictions need to be modified to provide this ability. The customization restrictions can be defined in: the XML schema definition, standalone XML file, tag library definition file, or an extended metadata file. Also check the customization policy for the MDS session in use and the customization configuration.

MDS-02404
The subelement {1} in the MDX document does not allow customization of {0}.

Category:
Configuration

Cause:
An attempt was made to customize a node that was not customizable.

Action:
Check the customization restriction information which can be located in the schema definition, standalone xml file or an extended metadata file. Also check the customization policy for the MDSSession in use and the customization configuration.

MDS-02405
The attribute {2} in element {1} in the MDX document does not allow customization of {0}.

Category:
Configuration

Cause:
An attempt was made to customize a node that was not customizable.

Action:
If the attempted customization is valid, the customization restrictions need to be modified to provide this ability. The customization restrictions can be defined in: the XML schema definition, standalone XML file or an extended metadata file. Also check the customization policy for the MDS session in use and the customization configuration.

MDS-02406
Customization of {0} is not allowed because it is not explicitly allowed by any type definition nor any extended metadata entry.

Category:
Configuration

Cause:
An attempt was made to customize a node that was not customizable.

Action:
If the attempted customization is valid, the customization restrictions need to be modified to provide this ability. The customization restrictions can be defined in: the XML schema definition, standalone XML file or an extended metadata file. Also check the customization policy for the MDS session in use and the customization configuration.

MDS-02407
Customization of {0} is not allowed because the local reference was not found in the document.

Category:
Programmatic

Cause:
An enquiry about the customizability of a node supplied a local reference that wasn't found in the document.

Action:
Ensure that the local reference applies to the document.

MDS-02408
The operation {0} on the {1} node is not allowed because the metadata object reference was not found in the change event.

Category:
Programmatic

Cause:
A document change is not allowed because the metadata object reference was null.

Action:
Ensure that the change document exists.

MDS-02500
Cannot find a valid MDSSession object for accessing the MDS document using ORAMDS URL

Category:
Programmatic

Cause:
A valid MDSSession object was not set before accessing the document using the "oramds:///" protocol.

Action:
Use the MDSURLHelper.setMDSSession() method to set a valid MDSSession object before accessing MDS documents using the oramds protocol.

MDS-02501
cannot load the ORAMDS URL "{0}" because MDS session could not be created or resolved

Category:
Programmatic

Cause:
An error occurred while creating or resolving an MDS session object.

Action:
Look for messages describing the cause exception in the error message log for more information on the actual reason for failure.

MDS-02600
configuration migration failure because the configuration document contains more than one mds-config element

Category:
Programmatic

Cause:
The given configuration document contained more than one mds-config element.

Action:
Correct the configuration document to contain a single mds-config element.

MDS-02601
configuration migration failure because it contains more than one persistence-config element

Category:
Programmatic

Cause:
The configuration document contained more than one persistence-config element.

Action:
Correct the configuration document to contain a valid persistence-config element.

MDS-02602
configuration migration failure because it contains more than one metadata-stores element

Category:
Programmatic

Cause:
The configuration document contained more than one metadata-stores element

Action:
Correct the configuration document to be a valid 10.1.3 configuration document.

MDS-02603
configuration migration failure because it contains an invalid metadata-store element

Category:
Programmatic

Cause:
The configuration document contained an invalid metadata-store element.

Action:
Correct the configuration document to be a valid 10.1.3 configuration document.

MDS-02700
The resource "{0}" cannot be updated by tenant "{1}".

Category:
Programmatic

Cause:
The given resource could not be updated by the current tenant because it was not available in current tenant's scope.

Action:
Verify that the resource is being updated in the same scope of the tenant who updates the resource.

MDS-02702
Tenant scoped PManager instance cannot be created for tenant {0} because given PManager instance does not have multitenancy enabled.

Category:
Configuration

Cause:
The PManager instance used here did not have multitenancy enabled but an attempt was made to create tenant scoped PManager instance.

Action:
Verify that the PManager instance being passed has multitenancy support enabled.

MDS-02703
Tenant scoped PManager cannot be created for tenant "null".

Category:
Configuration

Cause:
The PManager instance used here had multitenancy support enabled but an attempt was made to create tenant scoped PManager instance with "null" tenant.

Action:
Create scoped PManager instance for valid tenant id.

MDS-02704
Cannot create tenant scoped PManager instance using another tenant scoped PManager instance.

Category:
Programmatic

Cause:
An attempt was made to create tenant scoped PManager using another scoped PManager instance.

Action:
Create a tenant scoped PManager using an unscoped PManager instance.

MDS-02705
Cannot create PContext using an unscoped PManager instance.

Category:
Programmatic

Cause:
Creating PContext using an unscoped PManager instance was not allowed.

Action:
Use PManager instance that is scoped for a tenant to create PContext.

MDS-02706
Cannot create PTransaction using an unscoped PManager instance.

Category:
Programmatic

Cause:
Creating PTransaction using an unscoped PManager instance was not allowed.

Action:
Use PManager instance that is scoped for a tenant to create PTransaction.

MDS-02707
PContext with tenant id {0} cannot be used in scoped PManager with tenant id {1}.

Category:
Programmatic

Cause:
Tenant id attached to PContext and the tenant id of tenant scoped PManager to which it was passed did not match.

Action:
Create PContext from the tenant scoped PManager to which it is passed.

MDS-02708
PManager instance is being used after it has been released.

Category:
Programmatic

Cause:
PManager instance was being used after it had been released.

Action:
Create a new PManager.

MDS-02709
Configuration change operation "{0}" on scoped PManager is not allowed for the tenant {1}. Only global tenant is allowed to change the configuration settings in PManager.

Category:
Programmatic

Cause:
A non global tenant attempted to change configurations in scoped PManager.

Action:
Use global tenant scoped PManager to change the configuration settings.

MDS-02710
Operation "{0}" is not allowed in unscoped PManager.

Category:
Programmatic

Cause:
A tenant aware operation was invoked in an unscoped PManager instance.

Action:
Use a global or tenant scoped PManager to do the operation.

MDS-02711
No tenant operations are allowed on MetadataStoreConnection not associated with any tenant id.

Category:
Programmatic

Cause:
A tenant aware operation was invoked in MetadataStoreConnection to database store which did not have any tenant id attached.

Action:
Create a new MetadataStoreConnection with a valid tenant id.

MDS-02712
The operation {0} is not allowed in this MetadataStoreConnection to database store because the MetadataStoreConnection is not attached to any tenant id.

Category:
Programmatic

Cause:
A tenant aware operation was invoked in MetadataStoreConnection to database store which did not have any tenant id attached.

Action:
Create a new MetadataStoreConnection with a valid tenant id.

MDS-02713
PContext associated with tenant {0} cannot be used with MetadataStoreConnection associated with different tenant {1}. Operation {2} failure.

Category:
Programmatic

Cause:
The tenant id attached to PContext and MetadataStoreConnection did not match.

Action:
Use PContext with same tenant id as the one attached to metadata store connection.

MDS-02714
Creating metadata store connection for tenant {0} is not allowed in non multitenant application.

Category:
Programmatic

Cause:
An attempt was made to create metadata store connection for non global tenant in non multitenant application.

Action:
Use global tenant id to create metadata store connection.

MDS-02715
No tenant scoped PManager instances can be created on already released PManager instance.

Category:
Programmatic

Cause:
An attempt was made to create a tenant scoped PManager instance on already released PManager instance.

Action:
Create new PManager instance using a PConfig then try creating scoped PManager instance.

MDS-02720
Cannot rename the document {0} to {1} as the new tenant scope does not match the original tenant scope.

Category:
Programmatic

Cause:
The new name for the document was configured to a different tenant scope to the old document name.

Action:
Provide a new valid document name that maps to the same tenant scope as the original document.

MDS-02721
PResource {0} for tenant {1} cannot be used with MetadataStoreConnection that is associated with different tenant {2}. Operation {3} failure.

Category:
Programmatic

Cause:
The tenant ids of the PResource and the MetadataStoreConnection did not match.

Action:
Use PResource with same tenant id of the one attached to metadata store connection.

MDS-02722
Mar Lineage can be created by global tenant only. Creating MAR lineage is not supported for tenant {0}.

Category:
Programmatic

Cause:
A non-global tenant attempted to create MAR lineage which is not supported. MAR lineage creation is allowed only for global tenant currently.

Action:
Create MAR lineage from global tenant context.

MDS-02723
Operation "{0}" is not supported in Sandbox currently.

Category:
Programmatic

Cause:
Unsupported operation was invoked in Sandbox instance.

Action:
This operation is not supported in Sandbox currently.

MDS-02724
The ResourceName that is attached to tenant scope {0} is not allowed in SandboxPTransaction that is attached to the different tenant scope {1}. Operation {2} failure.

Category:
Programmatic

Cause:
Tenant scope for ResourceName and SandboxPTransaction did not match.

Action:
Use ResourceName with same tenant scope of the one attached to SandboxPTransaction.

MDS-02725
The Label {0} that is attached to tenant {1} is not allowed in MetadataStoreConnection that is attached to different tenant {2}. Operation {3} failure.

Category:
Programmatic

Cause:
Tenant id for Label and MetadataStoreConnection did not match.

Action:
Use label with same tenant id of the one attached to MetadataStoreConnection.

MDS-02726
The tenant {0} that is attached to PDocument {1} is not allowed in SandboxPTransaction that is attached to different tenant {2}. Operation {3} failure.

Category:
Programmatic

Cause:
Tenant id for PDocument and SandboxPTransaction did not match.

Action:
Use PDocument with same tenant id of the one attached to SandboxTransaction.

MDS-02727
The tenant {0} that is attached to Label {1} is not allowed in SandboxPTransaction that is attached to different tenant {2}. Operation {3} failure.

Category:
Programmatic

Cause:
Tenant id for Label and SandboxPTransaction did not match.

Action:
Use label with same tenant id of the one attached to SandboxPTransaction.

MDS-02728
The tenant {0} that is attached to {1} {2} is not allowed in Sandbox that is attached to different tenant {3}. Operation {4} failure.

Category:
Programmatic

Cause:
Tenant id attached and Sandbox did not match.

Action:
Use tenant id same as the one attached to Sandbox.

MDS-02729
The tenant scope {0} that is attached to {1} is not allowed in Sandbox that is attached to the different tenant scope {2}. Operation {3} failure.

Category:
Programmatic

Cause:
Tenant scope attached and Sandbox did not match.

Action:
Use tenant scope same as the one attached to Sandbox.

MDS-02730
Error in deprovisioning the tenant {0}. Unable to delete the resources in {1}.

Category:
Configuration

Cause:
Tenant resources might be on read-only store.

Action:
Verify that tenant resources exist on a writable store.

MDS-02731
Tenant specific operations cannot be done in multitenant disabled environment for tenant {0}.

Category:
Programmatic

Cause:
An attempt was made to do tenant specific operations in Multitenant disabled environment.

Action:
Enable the multitenant feature.

MDS-02732
TenantId cannot be created for the value "{0}".

Category:
Programmatic

Cause:
TenantId could not be created with negative values or a value with more than 18 digits.

Action:
Use positive values with max of 18 digits in decimal format to create a valid TenantId object.

MDS-02733
Rename across multiple tenant stripes is not supported on this store.

Category:
Programmatic

Cause:
The store does not support writing to multiple tenant stripes or multitenancy is not enabled.

Action:
Enable the multitenant feature.

MDS-02734
Unable to get TenantInfo for TenantId "{0}" from tenant management system.

Category:
Configuration

Cause:
Tenant is not yet provisioned or was deprovisioned from the POD.

Action:
Check tenant provisioning system to ensure tenant is provisioned.

MDS-02735
Label "{0}" cannot be deleted since it is attached to sandbox(es): "{1}".

Category:
Programmatic

Cause:
An attempt was made to delete a label that is attached to active sandbox(es).

Action:
Make sure that there are no sandboxes attached to label to be deleted. Refer to FMW Enterprise Manager MDS repository home page to check labels that are attached to a sandbox.

MDS-02736
Failed to update purge configuration value for tenant {0}.

Category:
Programmatic

Cause:
An error occurred while updating purge configuration.

Action:
Retry the operation. Also, refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-02737
Prevented potential duplicate tip version for document "{0}". Original request was to update document with PATH_DOC_ID={1}, PATH_VERSION={2} and PATH_LOW_CN={3}, updated latest tip version having PATH_DOC_ID={4}, PATH_VERSION={5} PATH_LOW_CN={6} to avoid duplicate tip version.

Category:
Programmatic

Cause:
MDS detected code flow which could have lead to duplicate tip issue.

Action:
Previous tip document is replaced forcefully with new content, validate content of the document.

MDS-02738
Database based metadata repository initialization failure because of invalid MDS database schema at "[{0}]".

Category:
Configuration

Cause:
Configured Database details refer to invalid or non-MDS schema.

Action:
Configure a valid MDS database schema created using Repository Creation Utility

MDS-02739
MDS Partition with ID {0} does not exist in the database repository

Category:
Programmatic

Cause:
This could be caused by deleting the partition while still being used by application.

Action:
Ensure partition is deleted only when not in use. To resolve the current issue, restart the application or server.

MDS-02740
MDS repository version for tenant "{0}" is not same as Global MDS repository version. Repository version for tenant is "{1}" whereas GLOBAL repository version is "{2}".

Category:
Configuration

Cause:
MDS Repository version for Tenant is not same as Global MDS repository version

Action:
Upgrade the MDS repository to the required version so that Global and Tenant repository versions are same.

MDS-02741
The metadata changes cannot be written to underlying store because read-only mode is enabled in the configuration.

Category:
Configuration

Cause:
An attempt to change metadata was made while changes were disabled for maintenance operations.

Action:
Reconfigure the application to not specify read-only mode in the configuration and use a writable metadata store to persist metadata changes.

MDS-02742
Instance of {0} is being used after it has been released.

Category:
Programmatic

Cause:
Instance of a MDS object was used after it was released.

Action:
Create a new instance.

MDS-02743
Error deleting partition {0} in repository {1}.

Category:
Configuration

Cause:
The directory or partition doesn't exist.

Action:
Verify that the metadata path or partition for the repository exists.

MDS-02744
Failed to delete directory {0}.

Category:
Programmatic

Cause:
The specified directory was invalid, read only or was in use and could not be deleted.

Action:
Check exception message in logs for the exception stack and underlying cause.

MDS-02745
Unable to get database connection from data source "{0}" for store id "{1}".

Category:
Configuration

Cause:
Failed to retrieve a database connection from the data source either because the data source is not configured correctly or the database details are not correct.

Action:
Check if the data source is configured correctly and the database is accessible. See message of the cause exception for more information on the actual reason for failure.

MDS-02746
Invalid store id.

Category:
Programmatic

Cause:
Store id is null or empty.

Action:
Provide a valid store id.

MDS-02747
Invalid data source.

Category:
Programmatic

Cause:
Data source cannot be null.

Action:
Provide a valid data source.

MDS-02800
The label "{0}" cannot be provided as null for label based transfer.

Category:
Configuration

Cause:
The label was provided as null for label based transfer.

Action:
Provide valid label name for label based transfer.

MDS-02801
Document {0} with scope {1} cannot be transferred by tenant {2}.

Category:
Programmatic

Cause:
The given document could not be transferred from source store by current tenant because the document was not in the scope of current tenant.

Action:
Ensure that document being transferred mapped to current tenant scope.

MDS-02802
Transfer is not supported for multitenant MDSInstance with file store.

Category:
Configuration

Cause:
Either source or target MDSInstance has multitenancy enabled and configured with file store.

Action:
Use a non multitanant MDSInstance with file store.

MDS-02803
List of patterns to select the MOs are either empty or null.

Category:
Programmatic

Cause:
List of MOPatterns are empty or null.

Action:
Ensure that valid list of MOPatterns are provided.

MDS-02804
Layer name "{0}" configured in CustLayerFilter to remove customizations, contains patterns.

Category:
Programmatic

Cause:
Layer name contains patterns.

Action:
Ensure that layer name doesn't contain any patterns.

MDS-02805
Import Metadata With Exact Copy is allowed only from archive.

Category:
Configuration

Cause:
Source MetadataStore was not not archive.

Action:
Use an archive as source store.

MDS-02806
Source archive is invalid because it is missing the export criteria metadata file.

Category:
Configuration

Cause:
MetadataFile containing the export criteria was missing in the source archive

Action:
Import from an archive which has metadata file.

MDS-02807
Import Metadata With Exact Copy is allowed only to Database repository

Category:
Configuration

Cause:
Target MetadataStore was not Database repository

Action:
Use Database repository as target for import.

MDS-02808
Category with which Export Criteria is written in the archive file is different from the one which is used to get ExportCriteriaReader

Category:
Configuration

Cause:
Wrong category was used to get Export Criteria Reader.

Action:
Use right category..

MDS-02809
Import Metadata With Exact copy operation is not supported when export criteria used to generate source archive contains fromLabel or toLabel conditions.

Category:
Configuration

Cause:
Export parameters fromLabel or toLabel were specified to generate archive that was acting as source for Import Metadata With Exact Copy Operation.

Action:
Use an archive MetadataStore that was exported without fromLabel or toLabel specified.

MDS-02810
Transfer operation with TransferType "{0}" has been aborted and rolled back because too many documents failed.

Category:
Other

Cause:
Operation failed for high number of documents.

Action:
Check the server logs to identify root cause, rerun the operation after correcting the issue in the system environment.

MDS-02811
Wrong TransferType {0} is passed in for Sandbox {1}

Category:
Configuration

Cause:
TransferType and TransferParams which is created for Sandbox transfer doesn't match.

Action:
Supply the right TransferType.

MDS-02812
Parameter {0} has null values in it.

Category:
Programmatic

Cause:
Parameter contains null values.

Action:
Ensure that the indicated parameter does not contain null values when the method is called.

MDS-02813
Parameter TransferOptions must be set when transferBaseDocument is set to false.

Category:
Programmatic

Cause:
Filtering out base documents is supported only when TransferOptions is set.

Action:
Ensure that TransferOptions is set when transferBaseDocument is set to false.

MDS-02814
Parallel Transfer of chunk {0} performed by thread {1} failed.

Category:
Other

Cause:
Error occured while transferring the chunk.

Action:
Check the server logs to identify root cause, rerun the operation after correcting the issue in the system environment.

MDS-02815
Parallel Transfer of one or more chunks timedout. Please retry transfer.

Category:
Other

Cause:
Timeout occured while transferring the chunk.

Action:
Check the server logs to identify root cause, rerun the operation after correcting the issue in the system environment.

MDS-05786
Unable to deploy the metadata archive: {0}.

Category:
Configuration

Cause:
Metadata archive (MAR) is corrupt.

Action:
Validate that the metadata archive (MAR) is valid and readable.

MDS-05787
Partition name is not specified in adf-config.xml file.

Category:
Configuration

Cause:
A property with name partition-name was not found as a child of the metadata-store element.

Action:
Specify the target partition as a child property of the metadata-store element in adf-config.xml.

MDS-05788
Unable to find the JNDI datasource in the file adf-config.xml.

Category:
Configuration

Cause:
A property with name jndi-datasource was not found as a child of the metadata-store element.

Action:
Specify the JNDI datasource a child property of the metadata-store element in adf-config.xml.

MDS-05789
Unable to deploy the metadata archive.

Category:
Configuration

Cause:
Metadata archive (MAR) was not found.

Action:
Ensure that the metadata archive (MAR) is packaged with the application.

MDS-05790
The metadata store definition is either missing or incorrectly specified in the application configuration.

Category:
Configuration

Cause:
The metadata store definition is either missing or incorrectly configured in the file adf-config.xml.

Action:
Ensure that the metadata store definition is present and contains the correct repository configuration

MDS-05791
An error occurred during the deployment of the metadata archive (MAR) {0}.

Category:
Configuration

Cause:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action.

Action:
Ensure that the metadata store configuration is correct.

MDS-05792
Unable to load MDS configuration from "{0}"

Category:
Configuration

Cause:
The MDS configuration is either not defined or incorrect.

Action:
Ensure that the MDS configuration is correctly defined.

MDS-05793
Metadata path {2} for partition {1} of MDS file repository {0} specified in adf-config.xml is either invalid or unreachable.

Category:
Configuration

Cause:
The metadata path named in the error message for the MDS file repository partition cited in the error message was either invalid or unreachable.

Action:
Ensure that the MDS file repository named in the error message is registered and that the metadata partition cited in the error message is configured with a valid metadata path in adf-config.xml.

MDS-05794
Unable to load MDS persistence configuration from "{0}"

Category:
Configuration

Cause:
The MDS persistence configuration is either not defined or incorrect.

Action:
Ensure that the MDS persistence configuration is correctly defined.

MDS-05795
Invalid value "{0}" specified in the content-config of the application's configuration

Category:
Configuration

Cause:
Only restriction type CUSTOMIZATIONS is supported in content-config.

Action:
Ensure that the MDS persistence configuration is correctly defined.

MDS-10001
Error:

Category:
Data

Cause:
An error occurred. Details are usually given in the accompanying messages.

Action:
Look for messages describing the cause and take the appropriate action.

MDS-10003
The specified {0} argument is null or empty.

Category:
Programmatic

Cause:
A required program argument was null or empty.

Action:
Record any accompanying exception messages and contact Oracle Support Services.

MDS-10009
The transfer of the document {0} is not successful.

Category:
Data

Cause:
Document transfer failed

Action:
Examine any accompanying messages to decide if further action is required.

MDS-10010
Deleting the document {0} is not successful.

Category:
Data

Cause:
Document deletion failed

Action:
Examine any accompanying messages to decide if further action is required.

MDS-10011
The operation on {0} has been rolled back. Total number of documents failed during the operation is {1}.

Category:
Data

Cause:
The transfer was rolled back

Action:
Examine any accompanying messages to decide if further action is required.

MDS-10012
The operation has failed.

Category:
Data

Cause:
The operation has failed.

Action:
Examine any accompanying messages to decide if further action is required.

MDS-10013
{0} operation started.

Category:
Data

Cause:
Transfer started.

Action:
Transfer started, no action required.

MDS-10014
{0} is completed. Total number of documents successfully processed : {1}, total number of documents failed : {2}.

Category:
Data

Cause:
Transfer complete.

Action:
Check any accompanying messages to decide if any action is required.

MDS-10015
Failure occurred while committing the {0} operation. The operation has been rolled back.

Category:
Data

Cause:
Failure occurred while committing the operation.

Action:
Examine any accompanying messages to decide if further action is required.

MDS-10016
The operation on {0} has been rolled back. The post transfer label {1} could not be created.

Category:
Data

Cause:
Failure occurred when creating the post transfer label.

Action:
Examine any accompanying messages to decide if further action is required.

MDS-10017
The target store does not support deployment management. Given application name "{0}" and deployment module name "{1}" could not be persisted as deployment information in store.

Category:
Data

Cause:
The target store does not support deployment management.

Action:
No action required. The documents will be transferred without the deployment information attached. If you want to store deployment information as well, configure a metadata store that supports deployment management, typically a DB store.

MDS-10018
The transfer restriction {0} is not supported in target store. All the documents will be transferred to target store.

Category:
Data

Cause:
Given transfer restriction is not supported in target store.

Action:
No action required. The given restriction will not be applied to the transfer, all the documents will be transferred to target store.

MDS-10019
The deployment information for application name "{0}" and module name "{1}" ignored since transfer operation is of type "{2}".

Category:
Data

Cause:
The deployment information will not be processed in transfer operation type other than "Deployment".

Action:
No action required. Given deployment information will not be processed in the current transfer operation.

MDS-10020
Querying checksum data from target repository to avoid transferring unchanged documents.

Category:
Data

Cause:
To apply transfer restriction CHANGED, transfer queries the target repository to check whether documents being transferred already exist with same content.

Action:
No action required.

MDS-10022
Query to get the checksum of the documents from target repository completed successfully.

Category:
Data

Cause:
To apply transfer restriction CHANGED, transfer queries the target repository to check whether documents being transferred already exist with same content.

Action:
No action required.

MDS-10023
No valid exclusion rules are specified in mds-transfer-config.xml to preserve documents in target store.

Category:
Data

Cause:
No valid namespaces or metadata object names specified in /meta-inf/mds-transfer-config.xml to preserve the documents in target store.

Action:
No action required.

MDS-10024
Preparing the list of documents to be excluded during transfer as per the configuration given in mds-transfer-config.xml.

Category:
Data

Cause:
To preserve the documents in target store as specified in the given /meta-inf/mds-transfer-config.xml, MDSTransfer prepares the list of documents to be excluded by looking at source and target stores.

Action:
No action required.

MDS-10025
Following metadata paths are configured in mds-transfer-config.xml to preserve existing documents under this metadata path in target repository. Configured metadata paths are as follows {0}:

Category:
Other

Cause:
Some metadata paths are configured in mds-transfer-config.xml to preserve existing documents in target repository.

Action:
No action required.

MDS-10026
Following Metadata object names are configured in mds-transfer-config.xml to preserve existing metadata objects with same name in target repository. Configured metadata object names are {0}:

Category:
Other

Cause:
Some metadata object names are configured in mds-transfer-config.xml to preserve existing documents in target repository.

Action:
No action required.

MDS-10027
To preserve documents in target store, the following documents from source store are marked as excluded by transfer {0}.

Category:
Other

Cause:
To preserve documents in target store, some documents from source store are marked as excluded by transfer.

Action:
No action required.

MDS-10030
Sandbox {0} created as part of Import operation is not destroyed after import failed.

Category:
Other

Cause:
A Critical Write error on database side has occurred. Look for specific exception in the log file.

Action:
Destroy unused sandbox from metadata repository. Contact application administrator for assistance.

MDS-10031
Value provided in {0} in CustLayerUsage or CustLayerFilter is not properly encoded.Passed in value will considered as it is without interpreting intended encoded value

Category:
Data

Cause:
Passed in value is not proper hexadecimal encoded value

Action:
No action required.

MDS-10032
Transfer operation with transfer type {0} ignoring document {1} because MDSInstance {2} reported it as not existing.

Category:
Programmatic

Cause:
MDSTransfer is configured to ignore such document.

Action:
No action required.

MDS-10033
Transfer operation with transfer type {0} has been rolled back because {1} documents failed with exceptions.

Category:
Other

Cause:
Operation failed for large number of documents due to exceptions.

Action:
Check the server logs to identify root cause, rerun the operation after correcting the issue in the system environment.

MDS-10034
Polling for store {0} failed - {1}. Polling will retry when the polling interval has elapsed.

Category:
Other

Cause:
The polling query was unable to run. If this is a temporary condition, polling should recover automatically once the error condition is resolved.

Action:
Polling will be retried. If problem persists enable tracing for oracle.mds.dbstore to get full stack trace and check datasources.

MDS-10035
Parallel transfer requested but not feasible, configure oracle.mds.transfer logger to FINEST to get more details.

Category:
Other

Cause:
Parallel transfer not supported for given transfer invocation.

Action:
Configure oracle.mds.transfer logger to FINEST to get more details.

MDS-11001
The type information for "{0}" is not obtainable though the document exists in the MetadataStore.

Category:
Data

Cause:
Could not get type information for a document, a possibly non-wellformed XML document.

Action:
Examine the document

MDS-11002
The type information for "{0}" is not obtainable because of exception "{1}"

Category:
Data

Cause:
Failed to get type information because an exception was raised.

Action:
Examine the exception and the document.

MDS-11003
Failed to force timestamp advance on file {0}: original timestamp = {1}, new timestamp = {2}.

Category:
Data

Cause:
Failed to advance the timestamp on a file which is being saved.

Action:
Examine the file and its permissions.

MDS-11006
Directory {0} does not exist.

Category:
Files

Cause:
The value of a name condition package did not have a corresponding file system directory.

Action:
Check if the directory was expected and determine why it is not present.

MDS-11007
Skipping directory {0} because {1} does not match the condition.

Category:
Programmatic

Cause:
The query considered the given directory, but it could only contain documents that would not match the query.

Action:
If you expected results from the directory, check that the query is correctly specified.

MDS-11008
Skipping directory {0} because it is a filestore root.

Category:
Files

Cause:
The query considered the directory, but it was another root path of the metadata store. This can arise when file store configuration includes multiple root paths and one of these is contained in another.

Action:
If you expected results from the directory, check that the file store is configured correctly.

MDS-11009
Skipping directory {0} because {1} is not a valid package name.

Category:
Programmatic

Cause:
The query skipped the directory because the corresponding package name is invalid.

Action:
If you expected results from the directory, check the directory name for validity.

MDS-11010
Document cache {0} exceeds its maximum number of entries {1}, so the cache is cleared.

Category:
Configuration

Cause:
The document cache exceeded its defined maximum size so it was cleared. If memory allows, the cache should be large enough for all documents for optimum performance but this is not required.

Action:
Edit the adf-config.xml file and increase the size of the document cache.

MDS-11011
Attempting to get failover connection to retry the operation because the database connection failed.

Category:
Configuration

Cause:
The connection to the database failed.

Action:
No action is required. The database is configured with FCF so failover will be attempted.

MDS-11012
Cache collision has been detected when adding key {0}, label set {1}, sandbox name {2}, scope {3}.

Category:
Programmatic

Cause:
The described document was being added to the cache, but it was already present. This can be caused by an incorrect miss in the preceding lookup, or very rarely by the document having been just inserted by another thread.

Action:
If this occurs frequently, contact Oracle Support Services.

MDS-11013
Cannot store the object of type {0} in the Java Object Cache because the cache or cache region is full

Category:
Configuration

Cause:
A CacheFullException or RegionFullException was reported when attempting to store an object in the Java Object Cache.

Action:
Consider increasing the size of the configured MDS Cache by modifying the cache-config entry in adf-config.xml.

MDS-11014
Purge-Repos Diagnostics [auto-purge, partition-name, partition-id, tenant-id, #versions purged]: [{0}, {1}, {2}, {3}, {4}].

Category:
Other

Cause:
An auto-purge occurred on a metadata-store.

Action:
No action required.

MDS-11016
MDS JSP Integration has been configured in Developer Mode to allow changes to files to be detected. Do not use this mode for production or performance testing.

Category:
Configuration

Cause:
Developer Mode is configured as a servlet initialization parameter either explicitly or because the application is being run within JDeveloper.

Action:
No action required.

MDS-11017
Started creating the final archive file at {0}.

Category:
Other

Cause:
ArchiveMetadataStore has started to create final archive file with all the changes done on the archive file so far.

Action:
No action required.

MDS-11018
The final archive file has been created successfully. The archive file is available at {0}.

Category:
Other

Cause:
ArchiveMetadataStore has created final archive file with all the changes done on the archive file so far.

Action:
No action required.

MDS-11019
The default CharSet {0} is not a unicode character set. File names with non-ASCII characters may not operate as expected. Check locale settings.

Category:
Configuration

Cause:
The Java default CharSet is used to convert file names to and from Java Strings. When this CharSet is a non-unicode character encoding, filenames that contain non-ASCII characters may not be correctly mapped to Java characters.

Action:
Check the locale environment variable settings for the process that is running the JVM that MDS is running in to ensure that a UTF encoding is being used. For example, the LC_ALL and LANG settings may be relevant.

MDS-11020
Cannot delete the intermediary archive file {0}.

Category:
Other

Cause:
The intermediary archive file could not be deleted.

Action:
Try deleting the file outside of MDS.

MDS-11023
MDS Remote Notifications: Coherence is not configured to use unicast and no cluster name is specified so remote notification is not enabled.

Category:
Configuration

Cause:
MDS remote notification only works if the Coherence configuration specifies unicast or a cluster name.

Action:
Unicast can be set by either specifying a unicast-listener in your Coherence cluster-config or by system property tangosol.coherence.wk. A cluster-name can be set either as part of a member-identity in your cluster-config or by system property tangosol.coherence.cluster.

MDS-11026
Ignoring the duplicate MDS component configuration file URL "{0}" found on the classpath.

Category:
Configuration

Cause:
A duplicate URL for an MDS component configuration file was found on the classpath.

Action:
No action required.

MDS-11027
Some metadata is configured to be stored as xml-stream. However it will be ignored because no metadata store configured for this application supports storing metadata in that form.

Category:
Configuration

Cause:
xml-stream content type was configured for some metadata content, but no metadataStore supports the feature.

Action:
No action required if not using xml-stream content type is acceptable. Otherwise, to enhance MDS repository performance, ensure that the metadata store supports xml-stream feature.

MDS-11028
Some metadata is configured to be stored as xml-stream. However it will be ignored because the corresponding metadata store, with class name: {0}, repository name: {1}, partition name: {2}, does not support storing metadata in that form.

Category:
Configuration

Cause:
xml-stream content type was configured for some metadata content, but the metadata store did not support the feature.

Action:
No action required if not using xml-stream content type is acceptable. Otherwise, to enhance MDS repository performance, ensure that the metadata store supports xml-stream feature.

MDS-11029
MetadataStore configuration for metadata-store-usage "{0}" is invalid. However the MetadataStore is ignored because it is not referenced by any namespace mapping.

Category:
Configuration

Cause:
MetadataStore class or some of its properties were not valid.

Action:
Ensure that the MetadataStore class exists and all required properties are valid.

MDS-11030
Failed to get schema version from registry for repository "{0}" because of exception: {1}

Category:
Configuration

Cause:
Either the DataSource definition for the repository is no longer valid or the MDS schema is not created using RCU.

Action:
Ensure the DataSource connection is valid or the schema is created using RCU.

MDS-11032
Registered grammar using remote schema "{0}". In design time (JDev) environment, it is recommended to use local resources.

Category:
Configuration

Cause:
Remote schema was referred with http URI. In design time environment, recommendation is to use local resources.

Action:
Replace it with local copy of schema.

MDS-11033
Duplicate mappings between namespace "{0}" and metadata store "{1}" are found in the persistence configuration.

Category:
Configuration

Cause:
There were more than one namespace to metadata store mappings for a given namespace in the persistence configuration.

Action:
Correct the namespace mapping in persistence configuration to ensure that the namespace is mapped to only one metadata store.

MDS-11034
The name {0} derived from JNDI will be registered as an MDS repository instead of the DataSource with the same name.

Category:
Configuration

Cause:
A JDBC DataSource and a JNDI have conflict in naming a MDS repository in the domain. MDS repository names must be unique within a domain.

Action:
Find out which application is referencing the repository and the JNDI name. Resolve the naming conflict by removing the DataSource with same name only if it is unused.

MDS-11100
MetadataObject.getBaseMO() found a mismatched CacheAccess in the cache. [refNoGUID={0}, guidRef={1}, mdxLookupKey={2}, isLabelledRead={3}, baseDocLabel={4}, setSandboxName={5}, cacheAccess={6}, doc={7}, name={8}, GUID={9}].

Category:
Other

Cause:
CacheAcces does not match the the given MOReference/Guid combination. The metadata object will not be cached.

Action:
Check the MOName and guid are correct and there are no duplicate Guids in the metadata store.

MDS-11101
MetadataObject.getBaseMO() recursing too deep. [refNoGUID={0}, guidRef={1}, mdxLookupKey={2}, isLabelledRead={3}, baseDocLabel={4}, setSandboxName={5}, cacheAccess={6}, doc={7}].

Category:
Other

Cause:
CacheAcces does not match the the given MOReference/Guid combination. The metadata object will not be cached.

Action:
Check the data in the metadata store to determine the cause.

MDS-11102
The MDS session was created by the ADF framework with a transaction key for its "single flush" feature, and the call to {0} is restricted to that framework. This call does not use that transaction key and although working now, will fail with an exception in future. To find the originator of the call, set the log level for logger "oracle.mds.transkey" to FINEST. Note that the ADF framework manages the MDS session created for the request so an explicit call to {0} should be removed.

Category:
Other

Cause:
A call was made to a restricted method on the MDS session and that call should be removed as it is liable to fail in later releases.

Action:
Identify the caller and ensure that the call to this method is removed.

MDS-11103
Failed to register dump classes.

Category:
Other

Cause:
Failed to register dump classes with DFW.

Action:
Contact Oracle Support Services.

MDS-11104
Content config mapping with path {0} contains reserved keyword "mdssys/cust/", use restrictionType="CUSTOMIZATIONS" instead.

Category:
Configuration

Cause:
The path of the content config mapping contains reserved keyword "mdssys/cust/".

Action:
Change the content config mapping to use restrictionType="CUSTOMIZATIONS"

MDS-11107
Unable to read "{0}" property value : "{1}". Cause : {2}

Category:
Configuration

Cause:
The property value contains invalid characters.

Action:
Correct the property value and retry.

MDS-11108
Invalid value supplied in "{0}" property value : "{1}".

Category:
Configuration

Cause:
The property value contains values that reduce the cache size to less than the minimum allowed.

Action:
Ensure the property values do not reduce the cache size to less than the minimum allowed.

MDS-11109
Successfully read property "{0}"="{1}" and generated "{2}".

Category:
Configuration

Cause:
Cache weightings successfully read.

Action:
No action required if the generated values are correct.

MDS-11110
customization-type will be ignored for mapping [Path to match={1}] because content-type is not configured in content-config.

Category:
Configuration

Cause:
content-type configuration is missing for mapping [Path to match={1}].

Action:
content-type must be configured as BINARY_STREAM (along with customization-type as FULL_REPLACE) for storing customizations as Layered Stream Object.

MDS-11111
Both ContentConfig and FileTypeConfig are configuring Content Type for file extension {0}, ContentType {1} from ContentConfig will override ContentType {2} from FileTypeConfig for path {3}.

Category:
Configuration

Cause:
ContentType configured in both Content Config and FileTypeConfig.

Action:
Correct the configuration to avoid the conflict.

MDS-90013
The metadata partition with name "{0}" does not exist in the metadata repository "{1}".

Category:
Topology

Cause:
The metadata partition with the specified name was not found in the metadata repository.

Action:
Create a metadata partition with the specified name in the metadata repository before trying this operation.

MDS-90014
cannot update the metadata because the application is read-only

Category:
Topology

Cause:
No metadata update was made because the ReadOnlyMode attribute was enabled.

Action:
Disable the ReadOnlyMode attribute of the target application configuration.

MDS-90015
The metadata repository with name "{0}" does not exist.

Category:
Topology

Cause:
The metadata repository with the specified name was not found.

Action:
Verify that the repository name is spelled correctly. If the repository does not exist, create one with the specified name and try again.

MDS-90016
There are no applications deployed to partition "{0}".

Category:
Topology

Cause:
An attempt was made to perform this operation on a partition that is not associated with a deployed application.

Action:
Specify a partition that is associated with a deployed application.

MDS-90017
The application to be used for this operation is not specified.

Category:
Topology

Cause:
Could not determine which application configuration to use for this operation since there is more than one application deployed to partition "{0}".

Action:
Specify an application that is deployed to partition "{0}" to be used for this operation.

MDS-90018
Application "{1}" is not deployed to partition "{0}".

Category:
Topology

Cause:
The specified application was not deployed to the specified partition.

Action:
Specify an application that is deployed to the partition.

MDS-90019
cannot set the user property on the driver: {0}

Category:
Topology

Cause:
A problem occurred while setting the user property on the driver.

Action:
Ensure that the database server is running properly.

MDS-90020
Metadata store cannot be assigned to server "{0}".

Category:
Topology

Cause:
A problem occurred while assigning resource to the server.

Action:
Ensure that the server is running properly.

MDS-90021
Metadata path {0} is invalid.

Category:
Topology

Cause:
The path used to create a FileMetadataStore was invalid. It must point to a directory.

Action:
Correct the metadata path.

MDS-90022
The host name of the database repository cannot be empty.

Category:
Topology

Cause:
The host name of the database repository was empty or null.

Action:
Use a valid host name.

MDS-90023
The database name of the database repository cannot be empty.

Category:
Topology

Cause:
The database name of the database repository was empty or null.

Action:
Use a valid database name.

MDS-90024
The user name of the database repository cannot be empty.

Category:
Topology

Cause:
The user name of the database repository was empty or null.

Action:
Use a valid user name.

MDS-90025
The password of the database repository cannot be empty.

Category:
Topology

Cause:
The password of the database repository was empty or null.

Action:
Use a valid password.

MDS-90026
The server name cannot be empty.

Category:
Topology

Cause:
The server name was empty or null.

Action:
Use a valid server name.

MDS-90027
cannot find server "{1}" to register the metadata repository "{0}"

Category:
Topology

Cause:
The server name was invalid.

Action:
Use a valid server name.

MDS-90028
Metadata repository with name "{0}" already exists.

Category:
Topology

Cause:
Metadata repository with the specified name already exists.

Action:
Verify that the repository name is spelled correctly. If the repository already exists, create one with a different name and try again.

MDS-90029
The metadata db repository with name "{0}" does not exist.

Category:
Topology

Cause:
The metadata db repository with the specified name was not found.

Action:
Verify that the db repository name is spelled correctly.

MDS-90030
The metadata file repository with name "{0}" does not exist.

Category:
Topology

Cause:
The metadata file repository with the specified name was not found.

Action:
Verify that the file repository name is spelled correctly.

MDS-90031
The JDBC resource of metadata db repository "{0}" cannot be found.

Category:
Topology

Cause:
The JDBC resource was not found.

Action:
Verify that the metadata db repository is set up correctly.

MDS-90032
The metadata store of metadata file repository "{0}" cannot be found.

Category:
Topology

Cause:
The metadata store was not found.

Action:
Verify that the metadata file repository is set up correctly.

MDS-90033
unknown DB vendor code: "{0}"

Category:
Topology

Cause:
The DB vendor code is invalid.

Action:
Use a valid DB vendor code, such as 0 (ORACLE), 1 (MSSQL), or 2 (IBMDB2).

MDS-90034
The source directory or archive "{0}" for importing metadata is invalid.

Category:
Topology

Cause:
The directory or archive location used to import metadata was invalid. It must point to a valid, existing directory or archive.

Action:
Correct the source directory or archive location.

MDS-90035
The target directory or archive "{0}" for exporting metadata is invalid.

Category:
Topology

Cause:
The directory or archive location used to export metadata was invalid. It must point to a valid location.

Action:
Correct the target directory or archive file location.

MDS-90036
The application does not have a valid MAR file path.

Category:
Topology

Cause:
The MAR path used to import MAR was invalid. It must point to a valid, existing MAR file.

Action:
Make sure the MAR file exists and is located in the correct directory of the application.

MDS-90037
The archive "{0}" does not contain valid contents.

Category:
Topology

Cause:
The archive used to import metadata was invalid. It must be to a valid, existing zip or jar file.

Action:
Make sure the archive is valid.

MDS-90038
The database authentication alias "{0}" already exists. To reuse the same authentication alias, try the operation again without specifying user and password.

Category:
Topology

Cause:
An attempt was made to configure a database authentication alias that already existed in Websphere server.

Action:
Delete the existing authentication alias and try again, or specify a new authentication alias, or reuse the existing authentication alias by not specifying user and password.

MDS-90039
The database authentication alias "{0}" cannot be found. To create the authentication alias, try the operation again with user and password specified.

Category:
Topology

Cause:
An attempt was made to use a database authentication alias that was not configured in Websphere server.

Action:
Make sure the specified database authentication alias is properly configured in Websphere server, or automatically create the authentication alias by specifying user and password.

MDS-90040
failed to connect to database

Category:
Topology

Cause:
An error occurred when trying to connect to database.

Action:
Make sure the database connection details are correct. Look at the cause exception for more details.

MDS-90041
Customization layer values are not supported for "excludeCustFor" parameter.

Category:
Topology

Cause:
One or more customization layer values was specified for "excludeCustFor" parameter.

Action:
Make sure there are no customization layer values specified for "excludeCustFor" parameter.

MDS-90042
"{0}" is not a valid tenant name.

Category:
Configuration

Cause:
The specified tenant was not provisioned in the specified partition and repository.

Action:
Specify a valid tenant name.

MDS-90043
This operation cannot be performed by the tenant named "{0}". It can only be invoked by the "{1}" tenant.

Category:
Configuration

Cause:
The specified tenant was not provisioned in the partition and repository provided.

Action:
Execute this operation as GLOBAL tenant.

MDS-90044
This operation cannot be performed because the WebLogic edit session has been locked by a different user.

Category:
Configuration

Cause:
The WebLogic edit session has been locked by a different user.

Action:
Retry the operation after the edit session lock is released.

MDS-90045
MDS dump operation "{0}" failed.

Category:
Data

Cause:
Exception occurred during the execution of the command.

Action:
Provide the required parameters for the command.

MDS-90046
MDS Application runtime MBean for application "{0}" running in server "{1}" is not available. "{2}" operation failure.

Category:
Configuration

Cause:
MDS Application runtime MBean was not available in the server.

Action:
Ensure the MDS Application runtime MBean for the application is available in the server. Ensure application name is correct.

MDS-90047
The target archive name "{0}" is invalid. It must point to a local file name with a valid archive extension.

Category:
Data

Cause:
The archive location used for mds dump operation was invalid.

Action:
Ensure target archive name is a valid local file name with valid archive extension.

MDS-90048
The dump argument "{0}" is invalid. It cannot be an empty string.

Category:
Data

Cause:
A request to execute dump was made with an invalid argument.

Action:
Ensure valid values are given for the dump arguments.

MDS-90049
Exclusion of documents during exportMetadata is not supported for seeded documents.

Category:
Data

Cause:
It was invalid to specify excludeDocs while not setting excludeSeededDos to true.

Action:
Either set excludeSeededDocs to true, or unspecify excludeDocs.

MDS-90050
ExportParameters can not be null for {0} operation.

Category:
Data

Cause:
ExportParameters with null value was not allowed.

Action:
Specify a valid ExportParameters argument.

MDS-90051
ImportParameters can not be null for {0} operation.

Category:
Data

Cause:
ImportParameters with null value was not allowed.

Action:
Specify a valid ImportParameters argument.

MDS-90052
Cannot deregister metadata repository "{0}" because it is based on a JNDI name of a consolidated data source.

Category:
Data

Cause:
The deregistration of a metadata repository that is based on a JNDI name of a consolidated data source is not allowed.

Action:
Perform deregistration operation on a metadata repository that is based on a non-consolidated data source only.

MDS-90053
Import Metadata With Exact copy operation is not supported when export operation used to generate source archive uses programmatic TransferListener.

Category:
Data

Cause:
Export parameter transferListener was specified to generate archive that was acting as source for Import Metadata With Exact Copy Operation.

Action:
Use an archive MetadataStore that was exported without programmatic TransferListener specified.

MDS-90054
The resource group "{0}" cannot not be found in "{1}" partition.

Category:
Data

Cause:
The specified resource group was not found in the current domain partition.

Action:
Verify that the specified resource group is defined in the current domain partition.

MDS-90055
The resource group must be specified to register a metadata repository at "{0}" partition.

Category:
Data

Cause:
The resource group was not specified to register a metadata repository at partition scope.

Action:
Specify a resource group for registering a metadata repository at the domain partition containing that resource group.

MDS-90056
{0} can not be null for {1} operation.

Category:
Data

Cause:
Null value was not allowed.

Action:
Specify a valid argument.

MDS-90057
The document name used in exportDocVersions operation is invalid.

Category:
Data

Cause:
Document pattern or empty document name was used.

Action:
Use the exact full document path.

MDS-90058
{0} operation is not permitted in Weblogic domain configured with consolidate schema or datasource.

Category:
Configuration

Cause:
It was unneccesary to register or deregister a metadata DB repository in consolidate Weblogic domain.

Action:
Use pre-configured metadata DB repository.

MDS-90059
A Metadata Archive (MAR) with the name {0} was found either packaged with the EAR or in directories listed in {1}.

Category:
Configuration

Cause:
Metadata Archive (MAR) names must be unique. Two or more metadata archives were found with the same name.

Action:
Use pre-configured metadata DB repository.

MDS-90060
A required JRF patch to support MSI-D was not applied in this env.

Category:
Other

Cause:
A JRF patch to enhance support for WebLogic Server MSI-D feature is missing in this env.

Action:
Apply the JRF Patch corresponding to the WLS MSI-D feature.

MDS-90061
The path denoted by "{0}" does not represent a Metadata Archive (MAR).

Category:
Other

Cause:
The path to a Metadata Archive (MAR) must represent a file with a "mar" extension.

Action:
Ensure that the Metadata Archive (MAR) path refers to a file with a "mar" extension in the application's EAR file.

MDS-90143
"{0}" is not a valid component name.

Category:
Configuration

Cause:
The specified component name is invalid.

Action:
Specify a valid audit component name that uses only letters.

MDS-90144
Error registering audit event definitions for component "{0}".

Category:
Configuration

Cause:
The audit event definitions could not be registered.

Action:
Refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-90145
Error occurred when raising audit event "{0}" for component "{1}".

Category:
Configuration

Cause:
The audit event was not registered or an unknown error occurred in the auditing system.

Action:
Refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-90146
Error occurred when checking if "{0}" is auditable.

Category:
Configuration

Cause:
An unknown error occurred when checking if auditing is enabled for the component "{0}".

Action:
Refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-90147
Error occurred when checking if the component "{0}" is auditable.

Category:
Configuration

Cause:
An unknown error occurred when checking if auditing is enabled for the event "{1}" defined for the component "{0}".

Action:
Refer to the error messages that describe the cause exception in the application logs for more information on the actual reason for failure.

MDS-90148
The custom audit event of type "{0}" was not audited because the event was not auditable according to the current audit policy.

Category:
Programmatic

Cause:
The custom audit event was either undefined in the audit configuration or it was not auditable according to the audit policy in effect.

Action:
Check the audit policy in effect.

MDS-90149
The custom audit event of type "{0}" was not audited because the MDSSession was not associated with a sandbox.

Category:
Programmatic

Cause:
The custom audit event was not audited because the current MDSSession was not associated with a Sandbox.

Action:
Use this API only when the custom audit event is intended to be raised in a sandbox context.

MDS-90243
Content auto merge failed for MO part "{0}" with change type "{1}" because its type is not registered for auto merge.

Category:
Programmatic

Cause:
The specified MOType is not registered for auto merge functionality.

Action:
Register the MOType for auto merge functionality.

MDS-90244
Content auto merge failed for MO part "{0}" with change type "{1}" because its base document is not accessible for read from any configured metadata stores.

Category:
Programmatic

Cause:
Base document is not accessible for read.

Action:
Make sure base document is available for read through any of configured metadata stores.

MDS-90245
Content auto merge failed for MO part "{0}" with change type "{1}" because both base and customization MOParts have conflicts and base MOPart is not a stub.

Category:
Programmatic

Cause:
Base MOPart is not a stub document.

Action:
This is unsupported case. Contact Oracle Support Services.

MDS-90246
Content auto merge failed for MO part "{0}" with change type "{1}" because mainline contains conflicting change type "{2}" for the same MOPart.

Category:
Programmatic

Cause:
There were conflicting changes for MetadataObject between sandbox and mainline and cannot be resolved by content auto merge.

Action:
Contact Application Administrator to resolve these conflicts manually or perform the changes again in a new sandbox.

MDS-90247
Content auto merge failed for MOPart "{0}" with change type "{1}", because conflicts identified for metadata object include changes for non tip or non configured customization layer "{2}".

Category:
Programmatic

Cause:
Conflicts detected for given metadata object include changes for non tip or non configured customization layer.

Action:
This is unsupported case. Contact Oracle Support Services.

MDS-90248
Content auto merge failed for MetadataObject "{0}".

Category:
Programmatic

Cause:
Content auto merge failed for specified MO.

Action:
Please check each MOPart exception for detailed reasons.

MDS-90249
Content auto merge failed for MetadataObject "{0}", because the MO constitutes more than one customization MOPart for the customization layer "{2}".

Category:
Programmatic

Cause:
Customization layer yields multiple layer values.

Action:
This is unsupported case. Contact Oracle Support Services.

MDS-90251
Conflict resolution hook annotation is missing for MOType {0}.

Category:
Configuration

Cause:
Conflict resolution policy was set to "callback" for the document type but associated Conflict resolution hook annotation configuration is missing.

Action:
Record the accompanying error and contact the developers of the application.

MDS-90252
Conflict resolution policy is either found missing or it's value is not set to "callback" for MOType {0}

Category:
Configuration

Cause:
Conflict resolution hook annotation was found in document type but conflict resolution policy configuration was either not supplied or the value was not set to "callback".

Action:
Record the accompanying error and contact the developers of the application.

MDS-90253
AutoMergePluginContext is null for AutoMergePlugin class {0}

Category:
Programmatic

Cause:
AutoMergePluginContext was found as null in AutoMergePlugin instance.

Action:
Record the accompanying error and contact the developers of the application.

MDS-90254
Unable to get AutoMergePlugin for MOType "{0}", Parameter AutoMergePluginContext must have a value.

Category:
Programmatic

Cause:
Parameter AutoMergePluginContext was null.

Action:
Record the accompanying error and contact the developers of the application.

MDS-90255
Conflict resolution hook class "{0}" cannot be instantiated for MOType "{1}"

Category:
Configuration

Cause:
An exception occurred while instantiating conflict resolution hook class.

Action:
Record the accompanying error and contact the developers of the application.

MDS-90256
Unable to get AutoMergePlugin instance from AutoMergePluginFactory for MOType "{0}".

Category:
Programmatic

Cause:
AutoMergePluginFactory returned null for AutoMergePlugin.

Action:
Record the accompanying error and contact the developers of the application.

MDS-90257
Unable to get AutoMergePluginFactory instance from ConflictResolutionHook for MOType "{0}".

Category:
Programmatic

Cause:
ConflictResolutionHook returned null for AutoMergePluginFactory.

Action:
Record the accompanying error and contact the developers of the application.

MDS-90258
Conflict resolution hook class "{0}" cannot be instantiated to get merge handler for MOType "{1}"

Category:
Configuration

Cause:
An exception occurred while instantiating conflict resolution hook class to get merge handler.

Action:
Record the accompanying error and contact the developers of the application.

MDS-90259
Unable to get MergeHandler instance from MergeHandlerFactory for MOType "{0}".

Category:
Programmatic

Cause:
MergeHandlerFactory returned null for MergeHandler.

Action:
Record the accompanying error and contact the developers of the application.

MDS-90260
Unable to get MergeHandlerFactory instance from ConflictResolutionHook for MOType "{0}".

Category:
Programmatic

Cause:
MergeHandlerFactory returned null for MergeHandlerFactory.

Action:
Record the accompanying error and contact the developers of the application.

MDS-90343
Sandbox "{0}" Apply operation failed for MO part "{1}" since conflict were identified with mainline changes for MO Part "{2}" that violates the relationship and dependency constraints.

Category:
Programmatic

Cause:
Sandbox changes violate some dependency constraints with mainline changes.

Action:
Contact Application Administrator to resolve these conflicts manually or perform the changes again in a new sandbox.

MDS-90344
Sandbox "{0}" apply operation with content auto merge failed.

Category:
Programmatic

Cause:
Sandbox apply operation with auto merge failed.

Action:
Please check each MO exception for detailed reasons.

MDS-90345
Failure to get conflicts for sandbox

Category:
Programmatic

Cause:
Target label is older than the sandbox mainline label.

Action:
Specify a target label which is later than current label.

MDS-90346
Invalid SandboxUsage. The sandbox name "{0}" in sandboxUsage does not match with Sandbox instance being operated upon.

Category:
Programmatic

Cause:
Wrong sandbox name used while retrieving MDSSession for conflict resolution.

Action:
Use right SandboxUsage that was used earlier for making the sandbox changes.

MDS-90347
Retry refresh operation on Sandbox "{0}" failed as it detected some unexpected mainline changes on MDSSession which is intended for conflict resolution, for following documents : {1}

Category:
Programmatic

Cause:
Unexpected mainline changes detected on MDSSession that was retrieved for conflict resolution during sandbox refresh operation.

Action:
Cancel mainline document changes from the MDSSession and retry the refresh operation.

MDS-90348
This operation cannot continue as Refresh is in progress for Sandbox {0}.

Category:
Programmatic

Cause:
Some other refresh operation might be in progress.

Action:
Cancel or End the in-progress refresh before trying this operation.

MDS-90349
This operation cannot continue as Refresh operation is either not initiated OR already ended for Sandbox {0}.

Category:
Programmatic

Cause:
Sandbox beginRefresh() hasn't been called.

Action:
Invoke the beginRefresh() first before this operation.

MDS-90350
This operation cannot continue as in progress refresh transaction is not yet completed for Sandbox {0}.

Category:
Programmatic

Cause:
Sandbox refresh operation hasn't ended using endRefresh() call.

Action:
Invoke the endRefresh() before trying this operation.

MDS-90351
Tip customization layer name and value are not defined for refresh operations for Sandbox {0}.

Category:
Programmatic

Cause:
Tip customization layer name and value are not defined.

Action:
Define tip customization layer name and value to perform sandbox refresh.

MDS-90352
Refresh operation cannot be ended since there are pending conflicts to resolve for Sandbox {0}.

Category:
Programmatic

Cause:
There are pending conflicts to resolve.

Action:
Resolve the pending conflicts and try the operation again.

MDS-90353
Sandbox name is null or empty.

Category:
Programmatic

Cause:
Sandbox name was null or empty.

Action:
Use a valid sandbox name that is not empty or null.

MDS-90500
Count of unresolved merge conflict(s) - {0}

Category:
Data

Cause:
One or more unresolved merge conflict(s) exists.

Action:
For more details, use getUnresolvedMergeConflicts() method on MOPartChangeContentAutoMergeException instance.

MDS-90501
Unexpected content auto-merge error

Category:
Programmatic

Cause:
An unexpected content auto-merge error occurred.

Action:
Please resolve the conflict before attempting auto-merge operation again.

MDS-90502
Invalid input documents for content auto-merge operation.

Category:
Data

Cause:
Invalid documents are provided to perform content auto-merge operation.

Action:
Provide valid documents.

MDS-90503
Limited support available for XSD content auto-merge operation.

Category:
Programmatic

Cause:
Unable to auto-merge changes being made by the request or by another user done to XSD metadata object.

Action:
Please resolve the conflict before attempting auto-merge operation again.

MDS-90504
No support to auto-merge updates done to elements with brittle local reference.

Category:
Data

Cause:
Updates done on elements with brittle local reference.

Action:
Resolve the conflict before attempting auto-merge operation again.

MDS-90505
Auto-merge synchronous XML tree walk failure occurred while handling following merge conflict - * {0}

Category:
Data

Cause:
An error occurred in the MDSDocumentAutoMergePlugin.

Action:
Check for log messages. If the problem persists, contact Oracle Support Services.

MDS-90506
No support to auto-merge move operation

Category:
Data

Cause:
Encountered move operation while performing content auto-merge operation.

Action:
Resolve the conflict before attempting auto-merge operation again.

MDS-90507
Type annotation "automerge" for child-list order preference on element with local reference "{0}" in metadata object "{1}" does not have valid value. Valid values are "childListOrderNotImportant" and "childListOrderImportant"

Category:
Data

Cause:
Child-list of the underlying element was modified as part of content auto-merge operation.

Action:
Provide valid value for "automerge" type-annotation. Valid values are "childListOrderNotImportant" and "childListOrderImportant".

MDS-90508
Type annotation automergeChildListOrderDefault set on element definition of root element in metadata object "{0}" does not have valid value. Valid values are "childListOrderNotImportant" and "childListOrderImportant".

Category:
Data

Cause:
Invalid value provided for automergeChildListOrderDefault type-annotation.

Action:
Provide valid value for automergeChildListOrderDefault type-annotation. Valid values are "childListOrderNotImportant" and "childListOrderImportant".

MDS-90540
Unable to automerge changes done to attribute on element "{0}" with local reference "{1}" since attribute "{2}" is inserted with different values "{3}" in the current transaction and "{4}" in another transaction.

Category:
Data

Cause:
Encountered element attribute automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90541
Unable to automerge changes done to attribute on element "{0}" with local reference "{1}" since attribute "{2}" is updated with different values "{3}" in the current transaction and "{4}" in another transaction.

Category:
Data

Cause:
Encountered element attribute automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90542
Unable to automerge changes done to attribute on element "{0}" with local reference "{1}" since attribute "{2}" is deleted in the current transaction but updated with value "{3}" in another transaction.

Category:
Data

Cause:
Encountered element attribute automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90543
Unable to automerge changes done to attribute on element "{0}" with local reference "{1}" since attribute "{2}" is updated with value "{3}" in the current transaction but deleted in another transaction.

Category:
Data

Cause:
Encountered element attribute automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90550
Unable to automerge changes done to text content of element "{0}" with local reference "{1}" since its text content is inserted with different values "{2}" in the current transaction and "{3}" in another transaction.

Category:
Data

Cause:
Encountered text content element automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90551
Unable to automerge changes done to text content of element "{0}" with local reference "{1}" since its text content is updated with different values "{2}" in the current transaction and "{3}" in another transaction.

Category:
Data

Cause:
Encountered text content element automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90552
Unable to automerge changes done to text content of element "{0}" with local reference "{1}" since its text content is deleted in the current transaction but updated with value "{2}" in another transaction.

Category:
Data

Cause:
Encountered text content element automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90553
Unable to automerge changes done to text content of element "{0}" with local reference "{1}" since its text content is updated with value "{2}" in the current transaction but deleted in another transaction.

Category:
Data

Cause:
Encountered text content element automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90560
Unable to automerge insertion of element "{0}" with local reference "{1}" under parent element "{2}" with local reference "{3}" since its fragment contents differ in the current transaction and in another transaction.

Category:
Data

Cause:
Encountered element insertion automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90561
Unable to automerge insertion of merge-unit "{0}" with local reference "{1}" under parent element "{2}" with local reference "{3}" since its fragment contents differ in the current transaction and in another transaction.

Category:
Data

Cause:
Encountered merge-unit insertion automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90562
Unable to automerge updates done to element "{0}" with local reference "{1}" under parent element "{2}" with local reference "{3}" since its fragment contents differ in the current transaction and in another transaction.

Category:
Data

Cause:
Encountered element update automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90563
Unable to automerge updates done to merge-unit "{0}" with local reference "{1}" under parent element "{2}" with local reference "{3}" since its fragment contents differ in the current transaction and in another transaction.

Category:
Data

Cause:
Encountered merge-unit update automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90564
Unable to automerge changes done to element "{0}" with local reference "{1}" under parent element "{2}" with local reference "{3}" since it is deleted in the current transaction but its fragment contents are updated in another transaction.

Category:
Data

Cause:
Encountered element automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90565
Unable to automerge changes done to merge-unit "{0}" with local reference "{1}" under parent element "{2}" with local reference "{3}" since it is deleted in the current transaction but its fragment contents are updated in another transaction.

Category:
Data

Cause:
Encountered merge-unit automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90566
Unable to automerge changes done to element "{0}" with local reference "{1}" under parent element "{2}" with local reference "{3}" since its fragment contents are updated in the current transaction but this element is deleted in another transaction.

Category:
Data

Cause:
Encountered element automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90567
Unable to automerge changes done to merge-unit "{0}" with local reference "{1}" under parent element "{2}" with local reference "{3}" since its fragment contents are updated in the current transaction but this merge-unit is deleted in another transaction.

Category:
Data

Cause:
Encountered merge-unit automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90568
Unable to automerge changes done to element "{0}" with local reference "{1}" since it is deleted in the current transaction but moved under a different parent in another transaction.

Category:
Data

Cause:
Encountered element automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90569
Unable to automerge insertion of element with local reference "{0}" in the current transaction since it is inserted under a different parent in another transaction.

Category:
Data

Cause:
Encountered element automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90570
Unable to automerge insertion of root element "{0}" with local reference "{1}" since its fragment contents differ in the current transaction and in another transaction.

Category:
Data

Cause:
Encountered element insertion automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90571
Unable to automerge insertion of root merge-unit "{0}" with local reference "{1}" since its fragment contents differ in the current transaction and in another transaction.

Category:
Data

Cause:
Encountered merge-unit insertion automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90572
Unable to automerge updates done to root element "{0}" with local reference "{1}" since its fragment contents differ in the current transaction and in another transaction.

Category:
Data

Cause:
Encountered element update automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90573
Unable to automerge updates done to root merge-unit "{0}" with local reference "{1}" since its fragment contents differ in the current transaction and in another transaction.

Category:
Data

Cause:
Encountered merge-unit update automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90574
Unable to automerge changes done to element "{0}" with local reference "{1}" since it is moved under a different parent in the current transaction but deleted in another transaction.

Category:
Data

Cause:
Encountered element automerge conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-90590
Unable to automerge updates done to element "{0}" with local reference "{1}" since its child order differs between the current transaction and another transaction.

Category:
Data

Cause:
Encountered child order conflict while performing content automerge.

Action:
Resolve the conflict before attempting automerge operation again.

MDS-91001
MDS domain runtime MBean is not available. "{0}" operation failure.

Category:
Configuration

Cause:
MDS domain runtime MBean was not available in the server.

Action:
Ensure the MDS domain runtime MBean is available in the server.

MDS-91002
MDS Application runtime MBean for "{0}" is not available. "{1}" operation failure.

Category:
Configuration

Cause:
MDS Application runtime MBean was not available in the server.

Action:
Ensure the MDS Application runtime MBean for the application is available in the server.

MDS-91003
Multiple MDSAppRuntimeMBean exist for "{0}". To execute the command, parameter "applicationVersion" is required. "{1}" operation failure.

Category:
Configuration

Cause:
Multiple MDSAppRuntimeMBean for the application were found in the server.

Action:
Provide the 'applicationVersion' parameter.

MDS-91004
MDS domain runtime MBean commands can be executed only from the Admin server. "{0}" operation failure.

Category:
Configuration

Cause:
WLST was not connected to the Admin server.

Action:
Connect to an Admin server before executing the command.

MDS-91005
No connection to a "{0}" server exists. The operation "{1}" can be executed only in the online mode.

Category:
Configuration

Cause:
Command was executed in the offline mode.

Action:
Ensure WLST is connected to the server.

MDS-91006
Expecting a "{0}" for parameter "{1}" but encountering "{2}". "{3}" operation failure.

Category:
Data

Cause:
Parameter type passed to the command was not correct.

Action:
Ensure the correct type of parameters are passed to the command.

MDS-91007
dbVendor should be one of ORACLE, MSSQL, IBMDB2, or MYSQL. "{0}" operation failure.

Category:
Data

Cause:
dbVendor value was not correct.

Action:
Ensure the dbVendor value is one of ORACLE, MSSQL, IBMDB2, or MYSQL.

MDS-91008
The "{0}" parameter is required. Provide a valid value and retry the operation.

Category:
Data

Cause:
Required parameter for the command was not given.

Action:
Provide the required parameters for the command.

MDS-91009
Operation "{0}" failure.

Category:
Data

Cause:
Exception occurred during the execution of the command.

Action:
Provide the required parameters for the command.

MDS-91010
The "adf-config" element is not available in the given archive file. "{0}" operation failure.

Category:
Configuration

Cause:
The "adf-config" element is not available in the given archive file.

Action:
Ensure the "adf-config" element is available in the adf-config.xml of the given archive file.

MDS-91011
No "mds-config" element exists in the adf-config.xml of the given archive. "{0}" operation failure.

Category:
Configuration

Cause:
No mds-config element existed in the adf-config.xml file of the archive file.

Action:
Ensure the "mds-config" element is available in the adf-config.xml file.

MDS-91012
Metadata repository connection type value should be either "File" or "DB". "{0}" operation failure.

Category:
Data

Cause:
Metadata repository connection type value is not correct.

Action:
Ensure the metadata repository connection type value is either 'File' or 'DB'.

MDS-91013
For the metadata repository''s DB connection type, JNDI location is a required parameter. "{0}" operation failure.

Category:
Data

Cause:
JNDI location not provided for DB connection type.

Action:
Provide the JNDI location string while updating the repository connection to DB.

MDS-91014
For the metadata repository''s File connection type, path location is a required parameter. "{0}" operation failure.

Category:
Data

Cause:
The path value was not provided for File connection type.

Action:
Provide the path location string while updating the repository connection to File.

MDS-91015
All parameters are required to update shared metadata repository configuration in adf-config.xml. At present, source archive has no connection details for the namespace "{0}". "{1}" operation failure.

Category:
Data

Cause:
Complete connection information was not provided to set the shared repository for the given namespace.

Action:
Provide complete connection information in case the adf-config.xml file does not have any metadata repository connection information for the given namespace already.

MDS-91016
All parameters are required to define new application metadata repository configuration in adf-config.xml. The source archive configuration does not contain any application metadata repository at present. "{0}" operation failure.

Category:
Data

Cause:
Complete connection information was not provided to set the application target repository.

Action:
Provide complete connection information in case the adf-config.xml does not have any metadata repository connection information for the application target repository already.

MDS-91017
The given namespace "{0}" to set the shared repository is not valid. Ensure that the namespace is available in the adf-config.xml file and it is not a sub-namespace of any other namespace. "{1}" operation failure.

Category:
Data

Cause:
The namespace provided to set the shared repository details is not valid.

Action:
Ensure that the namespace is available in the adf-config.xml file and it is not a subnamespace of any other namespace in that file.

MDS-91018
No namespaces are mapped to any shared repository in the source archive adf-config.xml configuration file. Shared repository details cannot be set. "{0}" operation failure.

Category:
Configuration

Cause:
No namespaces were mapped to any shared repository in the source archive adf-config.xml configuration file.

Action:
To set the shared repository connections, ensure at least one namespace is mapped to shared repository in the source archive adf-config.xml file.

MDS-91019
Multiple MDSAppRuntimeMBean exist for application "{0}". Ensure that the "application" "node" and "server" parameters are correct. "{1}" operation failure.

Category:
Configuration

Cause:
Multiple MDSAppRuntimeMBean for the application were found in the server.

Action:
Ensure that the "application" "node" and "server" parameters are correct.

MDS-91020
MDS Application runtime MBean for "{0}" is not available in server "{2}". Ensure server name and application name are correct. "{1}" operation failure.

Category:
Configuration

Cause:
MDS Application runtime MBean was not available in the server.

Action:
Ensure the MDS Application runtime MBean for the application is available in the server. Ensure the server name and the application name are correct.

MDS-91021
Multiple MDSAppRuntimeMBean exist for "{0}" in server "{2}". To execute the command, parameter "applicationVersion" is required. "{1}" operation failure.

Category:
Configuration

Cause:
Multiple MDSAppRuntimeMBean for the application were found in the server.

Action:
Provide the 'applicationVersion' parameter.

MDS-91022
Parameter "{0}" cannot be an empty string. "{1}" operation failure.

Category:
Data

Cause:
The parameter is not allowed to be an empty string.

Action:
Ensure the parameter has a correct value.

MDS-91023
Parameter "{0}" contains at least one empty element. "{1}" operation failure.

Category:
Data

Cause:
The parameter is not allowed to contain one or more empty elements.

Action:
Ensure every element specified in the parameter is correct.

MDS-91024
Parameters "{0}" and "{1}" cannot be specified at the same time.

Category:
Data

Cause:
The two parameters are not allowed to be specified at the same time.

Action:
Remove one of the parameters.

MDS-92000
Oracle Metadata Services schema upgrade is invalid.

Category:
Upgrade

Cause:
Specified Metadata Services schema was updated but is invalid.

Action:
Restore the Metadata Services schema from a backup and retry. Check the error messages in log file. Correct the problem before running the Assistant again.

MDS-92001
The upgrade is not supported from Oracle Metadata Services schema version of {0}.

Category:
Upgrade

Cause:
An unsupported base schema version was being upgraded.

Action:
Refer to the Oracle Metadata Services Upgrade Guide for supported versions to upgrade.

MDS-92002
Error in upgrading Oracle Metadata Services schema.

Category:
Upgrade

Cause:
An unexpected error occurred during Oracle Metadata Services schema upgrade.

Action:
Check the error messages in log file. Correct the problem before running the Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

MDS-92003
Error occurred while verifying the character set in target Metadata Services schema

Category:
Upgrade

Cause:
A SQL error occurred while verifying the character set in target Metadata Services schema.

Action:
Check the error messages in log file. Correct the problem before running the Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

MDS-92004
Error occurred while closing the resources during Metadata Services schema upgrade

Category:
Upgrade

Cause:
A SQL error occurred while closing the resources during Metadata Services schema upgrade.

Action:
Check the error messages in log file. Correct the problem before running the Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

MDS-92005
Error occurred while closing Metadata Services schema upgrade log files.

Category:
Upgrade

Cause:
An unexpected error occurred while closing Metadata Services schema upgrade log files.

Action:
Check the error messages in log file. Correct the problem before running the Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

MDS-92006
Oracle Metadata Service schema status is invalid.

Category:
Upgrade

Cause:
Specified Oracle Metadata Services database schema was invalid.

Action:
Check the error messages in log file. Correct the problem before running the Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

MDS-92007
Error occurred while verifying the user privileges in target Metadata Services schema

Category:
Upgrade

Cause:
A SQL error occurred while verifying the user privileges in target Metadata Services schema.

Action:
Check the error messages in log file. Correct the problem before running the Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

MDS-92008
The logon DBA user does not have sufficient privileges to upgrade the target Metadata Services schema user

Category:
Upgrade

Cause:
The logon DBA user needs to have grant execute privilege on specific DBMS packages to other users for upgrading the schema user privileges in target Metadata Services schema.

Action:
Logon as SYSDBA or other DBA users with sufficient privileges to grant execute on DBMS packages to other users and run the Assistant again.

MDS-92009
Oracle Metadata Services schema is not enabled for EBR.

Category:
Upgrade

Cause:
Specified Oracle Metadata Services database schema was not enabled for EBR.

Action:
Specify an Oracle Metadata Service schema that is enabled for EBR or Specify an upgrade for Oracle database type.

MDS-92010
Unable to continue due to an unexpected error

Category:
Upgrade

Cause:
An unexpected error occurred.

Action:
See the secondary error message for additional details.

19
NG-1010 to NG-2170

NG-1010
The archive location must be provided using the -archiveLoc option

Category:
Configuration

Cause:
The archive location option (-archiveLoc) was not provided.

Action:
include the -archiveLoc option during the execution.

NG-1020
The archive location must specify a file that does not exist but {0} already exists

Category:
Configuration

Cause:
The Archive jar that will be created, already exists and cannot be override.

Action:
Change the name of the archive jar or delete/move the file that already exists.

NG-1030
The Oracle Home location {0} does not exist

Category:
Configuration

Cause:
The ORACLE_HOME variable contains a location that does not exist.

Action:
Change the ORACLE_HOME variable to a valid location that exist.

NG-1040
Disk space insufficient

Category:
Memory

Cause:
The location provided to create the archive jar does not have enough disk space to create the file.

Action:
Release some disk space or change the location.

NG-1050
{0} cannot be accessed for write

Category:
Files

Cause:
When appending each file to the archive jar, the permissions file is being generated and the file is not accessible during that process.

Action:
Verify that the location provided has write permissions to create the archive.

NG-1060
Could not create the {0} file

Category:
Files

Cause:
The properties file cannot be written into the temporary location

Action:
Verify that the location provided has write permissions to create the properties file.

NG-1070
{0} could not be append to jar

Category:
Files

Cause:
When appending each installed OUI file to the archive jar one file was not able to be appended.

Action:
Verify that the location provided has write permissions to create the archive.

NG-1080
Manifest could not be created in {0}

Category:
Files

Cause:
To make the jar executable, a manifest is required to be append into the archive, if the Manifest creation was not possible will throw this message.

Action:
Verify that the location provided has write permissions to create the archive.

NG-1090
Manifest could not be append to jar

Category:
Files

Cause:
Appending the temporary manifest into the archive jar will throw an error if the jar is not accesible.

Action:
Verify that the location provided has write permissions to create the archive.

NG-1100
Clone permissions file could not be append to jar

Category:
Files

Cause:
Appending the temporary permissions file into the archive jar will throw an error if the jar is not accesible.

Action:
Verify that the location provided has write permissions to create the archive.

NG-1110
Unable to append executable classes to {0}

Category:
Files

Cause:
Appending the required executable classes into the archive jar will throw an error if the jar is not accesible.

Action:
Verify that the location provided has write permissions to create the archive.

NG-1120
Clone main class file could not be append to jar

Category:
Files

Cause:
Appending the main class into the archive jar will throw an error if the jar is not accesible.

Action:
Verify that the location provided has write permissions to create the archive.

NG-1130
Could not retrieve top level products from {0}

Category:
Files

Cause:
When using the option -includeDirs if one of the directories does not exists will send this message.

Action:
Verify that all the directories provided for option -includeDirs exist.

NG-1140
Unable to append files in directory {0} to jar {1}

Category:
Files

Cause:
If while appending files into the archive jar there was a problem reading the directory will throw this message.

Action:
Read the exception thrown for more details.

NG-1150
Could not process elements in directory {0} while appending to jar {1}

Category:
Files

Cause:
If while appending files into the archive jar there was a problem will throw this message.

Action:
Read the exception thrown for more details.

NG-1160
The archive location cannot be created inside the Oracle Home

Category:
Files

Cause:
The location where the archive will be created should not be inside the oracle home that will be clone.

Action:
Change the location of the archive to a place outside of the Oracle Home.

NG-2010
Oracle home is required

Category:
Configuration

Cause:
When the mandatory ORACLE_HOME variable was not provided.

Action:
Provide mandatory ORACLE_HOME variable.

NG-2015
Oracle home is already registered in the inventory

Category:
Configuration

Cause:
The mandatory ORACLE_HOME variable provided is already registered in inventory.

Action:
The Oracle Home provided should be change to a new one that is not registered in the inventory.

NG-2020
The output Oracle Home should be an empty directory

Category:
Configuration

Cause:
The mandatory ORACLE_HOME variable should be an empty directory not an already existing Oracle Home.

Action:
Change The Oracle Home provided to an empty location.

NG-2030
The output Oracle Home should be an absolute path

Category:
Configuration

Cause:
The mandatory ORACLE_HOME variable should specified as an absolute path.

Action:
Change ORACLE_HOME to an absolute path.

NG-2040
Archive location must be specified

Category:
Configuration

Cause:
The mandatory -archiveLoc option was not provided.

Action:
During the execution include the option -archiveLoc with the path to the archive file.

NG-2050
Problem loading archiveLoc {0}

Category:
Files

Cause:
The archive jar cannot be open for extraction.

Action:
Read the exception thrown for more details.

NG-2060
Problem creating required directories {0}

Category:
Files

Cause:
When there is a problem creating the path in the provided ORACLE_HOME directory.

Action:
Verify that the location provided for extraction has write permissions.

NG-2070
The package to extract should have an extension .jar

Category:
Configuration

Cause:
When the -archiveLoc does not end with ".jar" extension.

Action:
Change the option -archiveLoc to use a proper ".jar" file.

NG-2080
Problem opening archiveLoc {0}

Category:
Files

Cause:
If the extraction jar does not have permissions to be opened.

Action:
Read the exception thrown for more details.

NG-2090
Problem during extraction {0}

Category:
Files

Cause:
When one of the jar entries cannot be extracted into the Oracle Home.

Action:
Verify that the location provided for extraction has write permissions.

NG-2100
Problem loading next jar {0}

Category:
Files

Cause:
When the archive is created using the -maxArchiveSize option will create multiple jars, if one of the jar files does not have the permissions to open it will fail.

Action:
Change all the jar permissions so they can be extrated. Check the thrown exception to check which files need to be changed.

NG-2110
Disk space insufficient

Category:
Memory

Cause:
The location provided to create the Oracle Home does not have enough disk space to extract the files.

Action:
Release some disk space or change the location where the Oracle Home will be extracted.

NG-2120
Incompatible java version

Category:
Other

Cause:
The JAVA version required in the original Oracle Home is not compatible with the java version in the system where will be extracted.

Action:
Verify the Java version used during the creation of the archive inside the jar MANIFEST and use that version for extraction.

NG-2130
Problem extracting permissions file {0}

Category:
Files

Cause:
There is a permissions file in the archive to set the permissions as in the original Oracle Home, this will fail if there is a problem while updating those permissions.

Action:
Verify if you have permissions in the folder where the Oracle Home will be extracted to change the permissions of the files.

NG-2140
Failure to execute prerequisites phase. Review options -prereqConfigLoc and -entryPoint

Category:
Process

Cause:
When the process of prerequisites was not able to complete correctly.

Action:
Verify the log and check you are in compliance with all the prerequisites for the extracted Oracle Home

NG-2150
There was an error while parsing the command line, please check log for more details

Category:
Configuration

Cause:
The parameters provided for applyCloneArchive are incorrect. Please validate the options for applyCloneArchive.

Action:
Execute the jar with -help options and validate that all the options are valid.

NG-2160
Prerequisites file is missing

Category:
Configuration

Cause:
The -prereqConfigLoc provided is pointing to an incorrect prerequisite location.

Action:
Validate the -prereqConfigLoc contains the prerequisite files to validate during the Oracle Home creation.

NG-2170
There was an error during prerequisites initialization {0}

Category:
Process

Cause:
While preparing the arguments to create the prereq process there was an error in the arguments.

Action:
Read the exception thrown for more details.

20
OAM-00001 to OAM-36105

OAM-00001
Cannot parse the session token.

Category:
Other

Cause:
The session token appears to be invalid.

Action:
For more details, start logging at the FINE level.

OAM-00002
Error occurred while handling the request.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-00003
Request-Response handler configuration is incomplete.

Category:
Other

Cause:
A request handler mapping was missing.

Action:
Add the missing handler mapping to the configuration.

OAM-00004
Cannot initialize the Diagnostic Engine.

Category:
Other

Cause:

Action:

OAM-00005
Cannot locate the custom login page.

Category:
Other

Cause:
The custom login page was not found.

Action:
Verify the configuration.

OAM-00006
Cannot locate the configuration of the custom login page.

Category:
Other

Cause:
The custom custom login page was not specified in the configuration.

Action:
Add the custom login page location to the configuration.

OAM-00007
Cannot edit the custom login page

Category:
Other

Cause:
The file permissions of the custom login page do not allow write access.

Action:
Change the file permissions to allow write access.

OAM-00008
Cannot close the custom login page

Category:
Other

Cause:
The source code of the custom login page does not support closing of the login page.

Action:
Check the custom login page source code.

OAM-00009
Unable to parse the redirection URL

Category:
Other

Cause:
An error occurred while parsing the redirect URL due to bad encoding or invalid format.

Action:
For more details, start logging at the FINE level.

OAM-000010
Cannot add query params to map for logout redirection

Category:
Other

Cause:
URLDecoder throwing UnsupportedEncodingException

Action:
Check the AMLogoutResponseHandler - getQueryMap method code.

OAM-000011
Cannot parse the request token sent from client with User Agent {0} and IP Address {1}.

Category:
Other

Cause:
The request token appears to be invalid.

Action:
For more details, start logging at the FINE level.

OAM-000012
Cannot construct the request token.

Category:
Other

Cause:
Could not create OAM request token.

Action:
For more details, start logging at the FINE level.

OAM-000013
Cannot construct OAM session token.

Category:
Other

Cause:
Could not create SSO Session token.

Action:
For more details, start logging at the FINE level.

OAM-000014
{0} set in {1} must be an integer greater-than or equal to zero.

Category:
Other

Cause:
SwitchGetToPostLimit was set incorrectly for the authentications scheme.

Action:
Correct the SwitchGetToPostLimit challenge parameter within the authentication scheme.

OAM-02001
Retrieve SSO session operation failed.

Category:
Other

Cause:
Cannot retrieve the SSO session from the request context. Session might have expired.

Action:
For more details, start logging at the FINE level.

OAM-02002
Error while processing the submitted credentials.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-02003
Error while processing credential collection.

Category:
Other

Cause:
An internal error occurred.

Action:
Check the authentication scheme configuration.

OAM-02004
Error while processing authorization request.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-02005
Error while parsing the SSO session token.

Category:
Other

Cause:
Error while parsing the SSO session token. Wrong session token format.

Action:
Retry. If the error persists verify the key roll-over configuration.

OAM-02006
Insufficient authentication level to access the resource.

Category:
Other

Cause:
An insufficient authentication level was used to access the resource.

Action:
Step up the authentication level by re-authenticating to the required level.

OAM-02007
Insufficient privileges. Authorization Denied.

Category:
Other

Cause:
Insufficient privileges.

Action:
Check the authorization permissions.

OAM-02008
Password expired. Authentication failed.

Category:
Other

Cause:
Insufficient privileges.

Action:
Check the authorization permissions.

OAM-02009
Password reset required. Authentication failed.

Category:
Other

Cause:
Insufficient privileges.

Action:
Check the authorization permissions.

OAM-02010
User account is locked. Authentication failed.

Category:
Other

Cause:
Insufficient privileges.

Action:
Check the authorization permissions.

OAM-02011
No user account found. Authentication failed.

Category:
Other

Cause:
Insufficient privileges.

Action:
Check the authorization permissions.

OAM-02012
No user name password combination found. Authentication failed.

Category:
Other

Cause:
Insufficient privileges.

Action:
Check the authorization permissions.

OAM-02013
Password Policy action not supported by the client. Authentication failed.

Category:
Other

Cause:
Insufficient privileges.

Action:
Check the authorization permissions.

OAM-02052
SME Adapter initialization Failed.

Category:
Other

Cause:
SME adapter initialization failed.

Action:
Verify the SME configuration.

OAM-02053
Component {1} initialization Failed.

Category:
Other

Cause:
Component initialization failed.

Action:
Verify the server configuration.

OAM-02054
SSO session creation failed.

Category:
Other

Cause:
Session Management Engine error.

Action:
Check Session Management Engine error logs.

OAM-02055
Retrieve SSO session operation failed.

Category:
Other

Cause:
Session might be expired.

Action:
If the problem persists contact the administrator.

OAM-02056
An error occurred while parsing the server token.

Category:
Other

Cause:
TPE token parsing failed.

Action:
check Token Processing Engine logs.

OAM-02057
Wrong Flow Controller configuration for {1}

Category:
Other

Cause:
Wrong Flow controller configuration

Action:
Check flow controller class name and configuration.

OAM-02058
Event Flow goes in infinite loop.

Category:
Other

Cause:
Wrong configuration or too many allowed login attempts.

Action:
Check event flow configuration and login attempt configuration.

OAM-02059
Flow Controller Cannot handle Event

Category:
Other

Cause:
Wrong Flow controller configuration

Action:
Check error log more details.

OAM-02060
Flow Controller :{0} Cannot handle Event :{1}

Category:
Other

Cause:
Wrong Flow controller configuration

Action:
Check event to flow controller mapping.

OAM-02061
Event Handler error.

Category:
Other

Cause:
Wrong event handler configuration

Action:
Check error log more details.

OAM-02062
Event Handler cannot handle the event.

Category:
Other

Cause:
Wrong event handler configuration

Action:
Check event to event handler controller mapping.

OAM-02063
Event Handler :{0} Cannot handle Event :{1}

Category:
Other

Cause:
Wrong event handler configuration

Action:
Check event to event handler controller mapping.

OAM-02064
Authentication Error during policy matching.

Category:
Other

Cause:
Authentication Error

Action:
Check error log more details.

OAM-02065
Configuration Service Adapter initialization Failed.

Category:
Other

Cause:
SConfiguration Service failed.

Action:
Verify the system configuration file

OAM-02066
Event Factory is not configured create the requested event.

Category:
Other

Cause:
Wrong event factory configuration

Action:
Check error log more details.

OAM-02067
Wrong event configuration. No event handler specified for event {0}.

Category:
Other

Cause:
Wrong event factory configuration

Action:
Check error log more details.

OAM-02068
Error occurred while configuring the request cache.

Category:
Other

Cause:
Wrong request cache handler class configuration.

Action:
Check error log more details.

OAM-02069
Error occurred while loading cache handler for class Name {0}

Category:
Other

Cause:
Wrong request cache handler class configuration.

Action:
Check error log more details.

OAM-02070
An error occurred while loading server aliases.

Category:
Other

Cause:
TPE token parsing failed.

Action:
check system configuration if the aliases are set up properly logs.

OAM-02071
No host configuration found for the alias {0}.

Category:
Other

Cause:
TPE token parsing failed.

Action:
check system configuration if the aliases are set up properly logs.

OAM-02072
Ignoring failure during Identity Store operation.

Category:
Other

Cause:
Operation to read or update user attribute in Identity Store resulted in exception.

Action:
Check the availability of configured Identity Store.

OAM-02073
Error while checking if the resource is protected or not.

Category:
Other

Cause:
TPE token parsing failed.

Action:
check system configuration if the aliases are set up properly logs.

OAM-02074
Error while checking if the resource {0} is protected or not.

Category:
Other

Cause:
TPE token parsing failed.

Action:
check system configuration if the aliases are set up properly logs.

OAM-02075
Component {0} initialized successfully.

Category:
Other

Cause:
None

Action:
None

OAM-02076
{0} Engine initialized successfully.

Category:
Other

Cause:
None

Action:
None

OAM-02077
SSO Engine initialized Successfully.

Category:
Other

Cause:
None

Action:
None

OAM-02078
Processing Event {0}

Category:
Other

Cause:
None

Action:
None

OAM-02079
SSO session created with session ID {0} for request ({1})

Category:
Other

Cause:
None

Action:
None

OAM-02080
Cache data sync:{0} for request {1};

Category:
Other

Cause:
None

Action:
None

OAM-02081
Created {0} : {1}

Category:
Other

Cause:
None

Action:
None

OAM-02082
Diagnostic Engine Registration failed for Controller Collector.

Category:
Other

Cause:
Diagnostic Engine Registration failed.

Action:
None

OAM-02083
Diagnostic Engine Registration failed for Credential Collector Controller.

Category:
Other

Cause:
Diagnostic Engine Registration failed.

Action:
None

OAM-02084
Credential collection process success.

Category:
Other

Cause:

Action:
None

OAM-02085
Successfully validated the submitted credentials.

Category:
Other

Cause:

Action:
None

OAM-02086
{0}: processing Event:{1}.

Category:
Other

Cause:

Action:
None

OAM-02087
Policy ID : {0}

Category:
Other

Cause:

Action:
None

OAM-02088
Scheme result : {0}

Category:
Other

Cause:

Action:
None

OAM-02089
Is Resource Protected status : {0}

Category:
Other

Cause:

Action:
None

OAM-02090
Status : {0}

Category:
Other

Cause:

Action:
None

OAM-02091
Challenge URL : {0}

Category:
Other

Cause:

Action:
None

OAM-02092
Session Updation Failed

Category:
Other

Cause:

Action:
None

OAM-02093
Session response name {0} is reserved for OAM Server. Value for this response will not be updated in session.

Category:
Other

Cause:
A session response is configured with name that is internally reserved for OAM Server

Action:
Please change the name of the session response not to conflict with OAM Server reserved names

OAM-02094
Assert credential process success.

Category:
Other

Cause:
None

Action:
None

OAM-02095
Assert credential process failed.

Category:
Other

Cause:
None

Action:
None

OAM-02096
An error occurred while building the DAP token {0}.

Category:
Other

Cause:
Constructing the outgoing DAP token failed.

Action:
Check the key and parameters in token.

OAM-02097
An error occurred while decrypting the DAP token {0}.

Category:
Other

Cause:
Decrypting the incoming DAP token failed.

Action:
Check the key configuration.

OAM-02098
Cannot parse the DAP token.

Category:
Other

Cause:
Error occured while parsing the token.

Action:
Check the configuration.

OAM-02099
{0}: Event processing finished :{1} with status {2}.

Category:
Other

Cause:

Action:
None

OAM-02100
User account is disabled. Authentication failed.

Category:
Other

Cause:
Insufficient privileges.

Action:
Check the authorization permissions.

OAM-02101
An error occurred while creating impersonation session

Category:
Other

Cause:
Impersonation session creation failed

Action:
Check the create impersonation session event

OAM-02102
An error occurred in retrieving the grant

Category:
Other

Cause:
Unable to retrieve the grants

Action:
Check the grant permissions

OAM-02103
An error occurred in end impersonate session

Category:
Other

Cause:
Unable to do end impersonate session

Action:
Check the end impersonate session event

OAM-02104
An error occurred while creating subject for impersonatee

Category:
Other

Cause:
Authentication Exception thrown while creating subject for impersonatee

Action:
Check the createSubject method in SSOEngineController

OAM-02105
An error occurred in end impersonate session

Category:
Other

Cause:
Policy Manager Exception thrown while creating subject for impersonatee

Action:
Check the createSubject method in SSOEngineController

OAM-02106
An error occurred while terminating session

Category:
Other

Cause:
Unable to terminate session

Action:
Check the terminate session event

OAM-02107
An error occurred while enumerating session

Category:
Other

Cause:
Unable to enumerate session

Action:
Check the enumerate sessions event

OAM-02108
An error occurred while updating session attributes

Category:
Other

Cause:
Unable to update session

Action:
Check the update session attributes event

OAM-02109
An excluded resource is configured for OSSO agent.

Category:
Other

Cause:
Excluded resource configured for OSSO agents.

Action:
Update the MOD OSSO configuration to include the excluded resource in the public list.

OAM-02110
Event flow controller is executed in infinite loops.

Category:
Other

Cause:
Wrong configuration.

Action:
Check event flow controller configuration.

OAM-04001
Configuration parameter type mismatch. Param {0}. Expected type {1}. Actual type {2}

Category:
Other

Cause:
The configuration parameter type was invalid.

Action:
Validate the configuration parameter.

OAM-04002
Unsupported value for config parameter. Parameter {0} . Value {1}. {2}

Category:
Other

Cause:
The specified configuration parameter was not valid.

Action:
Validate the configuration parameter.

OAM-04003
OAM proxy started. Listening on port {0}.

Category:
Other

Cause:
The OAM proxy has started listening on the specified port.

Action:

OAM-04004
Read configuration parameter {0} = {1}.

Category:
Other

Cause:
The OAM proxy has loaded its configuration.

Action:

OAM-04005
Client connection accepted.

Category:
Other

Cause:
A client TCP/IP connection was accepted.

Action:

OAM-04006
Client connection closed. Connection id {0}.

Category:
Other

Cause:
A client TCP/IP connection was closed.

Action:

OAM-04007
Message received from client. Message {0}, Host : {1} Port : {2}.

Category:
Other

Cause:
A message was received from a client on the NAP channel.

Action:

OAM-04008
Message sent to client. Message {0}, Host : {1} Port : {2}.

Category:
Other

Cause:
A message was sent to a client on the NAP channel.

Action:

OAM-04009
New Outbound connection created with OAM Access Server.

Category:
Other

Cause:
An outbound connection was created with an OAM 10g server.

Action:

OAM-04010
Message received on outbound channel from OAM Access server. Message {0}, Host : {1} Port : {2}.

Category:
Other

Cause:
A message was received from an OAM 10g server.

Action:

OAM-04011
Message sent on outbound channel to OAM 10g Access server. Message {0}, Host : {1} Port : {2}.

Category:
Other

Cause:
A message was sent to an OAM 10g server.

Action:

OAM-04012
Outbound connection closed.

Category:
Other

Cause:
A connection with an OAM 10g server was closed.

Action:

OAM-04013
Unexpected message received from client. Message {0}

Category:
Other

Cause:
An unexpected message was received when a simple mode handshake message from the client was expected.

Action:
Check the NAP mode configuration of the WebGate and the Server.

OAM-04014
Malformed message received from client. Details {0}

Category:
Other

Cause:
The length of message received from client was less than 0.

Action:
Restart the WebGate if the message is being received repeatedly.

OAM-04015
Outbound connection to Access Server not found.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04016
Session ID is missing in AmResponse

Category:
Other

Cause:
The session ID was not present in the OAM token.

Action:
Retry the request.

OAM-04017
OAM proxy end point activation failed. Exception:

Category:
Other

Cause:
The specified listening port is not available, or is aldready being used.

Action:
Restart the server or contact the system administrator.

OAM-04018
Required configuration parameter missing. Required {0}

Category:
Other

Cause:
The required configuration parameters were missing.

Action:
Verify the configuration.

OAM-04019
Work manager JNDI lookup failed. Exception:

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04020
Exception encountered while processing the request message:

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04021
NMP initialization failed.

Category:
Other

Cause:
The NAP handshake with the client failed or an unsupported application was trying to connect to the OAM proxy.

Action:
Verify the client version.

OAM-04022
SSL configuration is not specified for SIMPLE or CERT mode

Category:
Other

Cause:
The SSL configuration was required but not supplied for the SIMPLE or CERT mode.

Action:
Verify the SSL Configuration and rerun the operation.

OAM-04023
SSL handshake failed. Exception:

Category:
Other

Cause:
The NAP handshake with a client was not successful.

Action:
Check the client configuration.

OAM-04024
Exception in outbound message processing. Cause {0} . Message details {1}

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04025
Error in connecting to Access server. {0}

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04026
Error in NAP handshake with AAA server {0}

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04027
Cannot create Executor instance

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04028
Outbound Resource Adapter initialization error. {0}

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04029
Error in generating AMEvent. Details {0}

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04030
Partner lookup failed. Partner id {0}

Category:
Other

Cause:
The retrieval of partner metadata during client authentication was not successful.

Action:
Check if the partner is registered with the Access Server.

OAM-04031
NAP version mismatch during the NAP handshake. Client Message {0}

Category:
Other

Cause:
An unsupported NAP version was sent by the client.

Action:
Check the client configuration and version. Older clients may need to be upgraded.

OAM-04032
PAT API error. Details {0}

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04033
Error in retrieving secret information. {0} {1}

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04034
Token Cache Enabled.

Category:
Other

Cause:
Information message indicating that the token cache is enabled.

Action:

OAM-04035
Error while reading token cache size from configuration.

Category:
Other

Cause:
The cache configuration was invalid.

Action:
Fix cache configuration and rerun the operation.

OAM-04036
Channel security mode is different as specified in configuration {0}

Category:
Other

Cause:
The agent tried to communicate in a mode different from its configuration.

Action:
Check the agent mode. This may be a security issue if the configuration mode of agent is correct.

OAM-04037
Exception encountered while processing the HTTP message in OAM proxy:

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-04038
OAM proxy configuration parameter SSOOnlyMode is set to true. OAM proxy will skip authorization.

Category:
Other

Cause:
OAM proxy configuration parameter SSOOnlyMode is set to true.

Action:

OAM-04039
Agent {0} not privileged to invoke OPCODE {1}

Category:
Other

Cause:
Agent is not privileged to invoke the operation.

Action:
Check the agent configuration.

OAM-04040
Target Resource is not as expected. Target Resource {0} WebGate resource {1}

Category:
Other

Cause:
Target resource is not as expected. This issue may occur in session scope operations.

Action:
Runtime check failure. Check server logs.

OAM-04041
Failed to retrieve valid session from OAM Identity Assertion. Assertion {0}

Category:
Other

Cause:
Either invalid assertion was specified or session corresponding to assertion is invalid.

Action:
Please see logs for more details.

OAM-04042
Failed to check token issuance policy. Resource: {0}. Requestor: {1}

Category:
Other

Cause:
Evaluation of Token Issuance Policy failed.

Action:
Check Token Issuance Policy.

OAM-04043
Request is not processed. Access management service is disabled.

Category:
Other

Cause:
Access management service is not enabled on server.

Action:
Enable the access management service. Set oam proxy global parameter "10gCompatibleGetHostIdentifiersSupport" to true.

OAM-06001
Cannot parse the session token.

Category:
Other

Cause:
The session token is invalid or the wrong decryption key is present in the configuration.

Action:
Verify the key roll-over configuration.

OAM-10001
Cannot load the configuration file.

Category:
Other

Cause:
The configuration file location was invalid.

Action:
Verify the location of the configuration file.

OAM-10002
Cannot initialize the PAT Adapter.

Category:
Other

Cause:
The PAT configuration was invalid.

Action:
Verify the PAT configuration.

OAM-10003
Cannot initialize the Cache Handlers.

Category:
Other

Cause:
The request cache handler configuration was invalid.

Action:
Verify the request cache handler configuration.

OAM-10004
Cannot initialize the Controller.

Category:
Other

Cause:
The configuration for Controller events was invalid.

Action:
Verify the Controller configuration.

OAM-10005
Cannot initialize the Controller.

Category:
Other

Cause:
The configuration for the Flow controllerd was invalid.

Action:
Verify the Controller configuration.

OAM-10006
Cannot initialize the Controller.

Category:
Other

Cause:
The configuration for the Flow Mapping was invalid.

Action:
Verify the Controller configuration.

OAM-10007
Cannot initialize the Controller.

Category:
Other

Cause:
The configuration for the Event Handlers was invalid.

Action:
Verify the Controller configuration.

OAM-10008
Cannot initialize the Controller.

Category:
Other

Cause:
The configuration for the Event UI was invalid.

Action:
Verify the Controller configuration.

OAM-10009
Cannot initialize the Controller.

Category:
Other

Cause:
The Event Handler configuration was invalid.

Action:
Verify the Controller configuration.

OAM-10010
Cannot initialize the Controller.

Category:
Other

Cause:
The Event Factory configuration was invalid.

Action:
Verify the Controller configuration.

OAM-10011
An invalid Cookie Domain

Category:
Other

Cause:
The cookie domain was invalid.

Action:
Verify the configuration file.

OAM-10012
Cannot load audit configuration.

Category:
Other

Cause:
The audit configuration was invalid.

Action:
Verify the audit configuration.

OAM-10013
Cannot load audit configuration.

Category:
Other

Cause:
Mismatch between logger and resource configuration.

Action:
Verify the audit configuration.

OAM-10014
Invalid done URL specified during logout - {0}.

Category:
Other

Cause:
Done URL specified during logout is not in proper URL format.

Action:
Verify the done URL.

OAM-10015
Cache Info :: operation="{0}" paramName="{1}", paramDetail="{2}".

Category:
Other

Cause:
Displayed when the cache is operating.

Action:
None.

OAM-10016
Cache entry expired.

Category:
Other

Cause:
Displayed on expiry of the cached element.

Action:
None.

OAM-10017
Cannot intialize the server key.

Category:
Other

Cause:
Unable to retrieve server key from configuration.

Action:
Verify the configuration.

OAM-10018
No credcollect req resp handler specified

Category:
Other

Cause:
No credcollect req resp handler specified

Action:
Verify configuration cred collect req resp handler

OAM-12001
Cannot load audit configuration.

Category:
Other

Cause:
The specified configuration file does not exist, or the audit configuration is invalid.

Action:
Check the server error logs.

OAM-12002
User name value specified for special user is invalid.

Category:
Other

Cause:
The input value format is invalid, or exceeds 30 characters.

Action:
Correct the input value.

OAM-12003
Maximum directory size specified is invalid.

Category:
Other

Cause:
The input value format is invalid, is less than 1 or exceeds 1024.

Action:
Correct the input value.

OAM-12004
Maximum file size specified is invalid.

Category:
Other

Cause:
The input value format is invalid, is less than 1 or exceeds 1024.

Action:
Correct the input value.

OAM-12005
Map of audit events is invalid.

Category:
Other

Cause:
The audit event configuration is missing, or invalid.

Action:
Verify the configuration.

OAM-12006
Invalid path for audit event definitions file.

Category:
Other

Cause:
The audit event definitions file location is incorrect.

Action:
Verify the configuration.

OAM-12007
Invalid path for audit bustop directory.

Category:
Other

Cause:
The audit bustop location is missing, or invalid.

Action:
Verify the configuration.

OAM-12501
Getting ServerTokenMapper for: {0}.

Category:
Other

Cause:
Getting ServerTokenMapper for {0}

Action:
None

OAM-12502
Server Token Not available in the Response.

Category:
Other

Cause:
Server Token Not available in the Response.

Action:
None

OAM-12503
10g SSO_ID Token set {0} .

Category:
Other

Cause:
10g SSO_ID Token set.

Action:
None

OAM-12504
10g SSO_ID Decrypted successfully : {0}

Category:
Other

Cause:
10g SSO_ID Decrypted successfully.

Action:
None

OAM-12505
Removing the SSO_ID Cookie at Logout.

Category:
Other

Cause:
Removing the SSO_ID Cookie at Logout.

Action:
None

OAM-12506
"Creating session token with values - " + "Domain: {0}, Version: {1}, Age: {2}, Secure: {3}, " + "Value: {4}";

Category:
Other

Cause:
Created Session Token with values

Action:
None

OAM-12507
Token Version not found.

Category:
Other

Cause:
Token Version not found.

Action:
Validate the config to include the Token Version.

OAM-12508
10g SSO_ID Decryption failed.

Category:
Other

Cause:
10g SSO_ID Decryption failed.

Action:
Verify if the 10gSSO Server Key is present in the config

OAM-12509
Could not get token mapper for token for {0}.

Category:
Other

Cause:
Could not get token mapper for token.

Action:
Validate the config to include the Token Version.[v1.2, v1.4]

OAM-12510
10g SSO_ID Token NOT created.

Category:
Other

Cause:
10g SSO_ID Token NOT created.

Action:
Verify if the 10gSSO Server Key/Token Version is present in the config

OAM-12511
Error while creating SSO Transport token.

Category:
Other

Cause:
Error while creating Transport Token

Action:
Validate the config to check for the 10g SSO Server Key

OAM-12512
Cannot retrieve the 10g SSO Key

Category:
Other

Cause:
Cannot retrieve the 10g SSO Key

Action:
Validate the config to check for the 10g SSO Server Key

OAM-12513
Diagnostic Engine Failed to Start

Category:
Other

Cause:
Diagnostic Engine Failed

Action:
None

OAM-12514
Request Handling Error

Category:
Other

Cause:
Request Handling Error

Action:
None

OAM-12515
Session Token Not Found

Category:
Other

Cause:
Session Token Not Found

Action:
None

OAM-12516
10g SSO Server Config Details Missing

Category:
Other

Cause:
10g SSO Server Config Details Missing

Action:
Add the Config details to oam-config.xml

OAM-12517
OSSO 10g Server coexist token version configured does not match runtime token version

Category:
Other

Cause:
10g SSO Server coexist token version and runtime token versions does not match.

Action:
Update the OSSO 10g coexist token version to match the runtime version

OAM-14001
Unregistration of OAM Management MBean failed.

Category:
Other

Cause:
An internal error occurred.

Action:
Check the OAM Server logs.

OAM-14002
OAM Server configuration update failed.

Category:
Other

Cause:
Failed to update OAM Policy or System Configuration.

Action:
Check the OAM Server MBean logs.

OAM-14003
Invalid HostIdentifier configuration for AppDomain {0} in OAM Policy.

Category:
Other

Cause:
Definition of HostIdentifier for application domain was invalid.

Action:
Re-check Application Domain configuration in OAM Policy.

OAM-14005
Validation of a input parameter failed.

Category:
Other

Cause:
One of the input parameter value was illegal.

Action:
Check the OAM Server MBean logs.

OAM-14007
Cannot retrieve OAM Server configuration for {0}.

Category:
Other

Cause:
Cannot retrieve data from OAM System configuration.

Action:
Check the OAM Server MBean logs.

OAM-14008
Partner configuration for {0} already exist in system config.

Category:
Other

Cause:
A partner is already configured.

Action:
Delete existing partner or create partner with a different id.

OAM-14009
Application Domain not found in OAM Policy {0}.

Category:
Other

Cause:
None

Action:
None

OAM-14100
Host Information is already registered in OAM HostIdentifier with host {0} and port {1}.

Category:
Other

Cause:
None

Action:
None

OAM-14101
Starting Enable OIM Configuration.

Category:
Other

Cause:
None

Action:
None

OAM-14102
Starting Disable OIM Configuration.

Category:
Other

Cause:
None

Action:
None

OAM-14103
Completed OAM Server Policy Configuration update.

Category:
Other

Cause:
None

Action:
None

OAM-14104
Completed OAM Server System Configuration update.

Category:
Other

Cause:
None

Action:
None

OAM-14105
Completed OIM Configuration.

Category:
Other

Cause:
None

Action:
None

OAM-14106
Completed validation of Input values.

Category:
Other

Cause:
None

Action:
None

OAM-14107
Successfully updated OAM Partner data.

Category:
Other

Cause:
None

Action:
None

OAM-14108
Successfully updated OAM Configuration.

Category:
Other

Cause:
None

Action:
None

OAM-14109
Enables OIM Integration.

Category:
Other

Cause:
None

Action:
None

OAM-14110
Disables OIM Integration.

Category:
Other

Cause:
None

Action:
None

OAM-14111
Registration of OAM Management MBean failed.

Category:
Other

Cause:
An internal error occurred.

Action:
Check the OAM Server logs.

OAM-14112
Gets the manage server host, NAP port.

Category:
Other

Cause:
None

Action:
None

OAM-14113
Updates OIM host and port.

Category:
Other

Cause:
None

Action:
None

OAM-14114
Error in getting the OAM server info.

Category:
Other

Cause:
None

Action:
None

OAM-14115
Create and configure OAM partner.

Category:
Other

Cause:
None

Action:
None

OAM-16001
Cannot parse the session token.

Category:
Other

Cause:

Action:

OAM-18001
User Identity Store Configuration is not valid.

Category:
Other

Cause:
The user identity store configuration was missing, or was invalid.

Action:
Verify the user identity store configuration.

OAM-18002
Error while reading User Identity Store Configuration.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18003
Error while reading User Identity Store Configuration attribute "{0}".

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18004
User Identity Store name passsed as NULL during user identity store read operation.

Category:
Other

Cause:
User Identity Store name passsed to read operation was null.

Action:
Rerun with actual object.

OAM-18005
User Identity Store ID passsed as blank during user identity store read operation.

Category:
Other

Cause:
User Identity Store ID passsed to read operation was blank.

Action:
Rerun with a valid ID.

OAM-18006
Map of Properties passed as NULL during user identity store create operation.

Category:
Other

Cause:
Map of Properties passed to create operation was null.

Action:
Rerun by passing Map of properties.

OAM-18007
Empty Map of Properties passed during user identity store create operation.

Category:
Other

Cause:
Map of Properties passed to create operation was empty.

Action:
Rerun by passing Map of properties.

OAM-18008
NULL passed during user identity store modify operation.

Category:
Other

Cause:
Object passed to modify operation was null.

Action:
Rerun with actual object.

OAM-18009
Validation Failure - an User Identity Store named "{0}" already exists.

Category:
Other

Cause:
User Identity Store names must be unique.

Action:
Choose a different name for this User Identity Store.

OAM-18010
Exception while encrypting the credetial for User Identity Store.

Category:
Other

Cause:
Exception while encrypting the crendential for User Idenity Store.

Action:
For more details, start foundation config logging at FINE level.

OAM-18011
Validation Failure - User Identity Store "{0}" is referred in following authentication schemes : "{1}".

Category:
Other

Cause:
User Identity Store is referred in authentication schemes.

Action:
Delete or change the reference of this User Identity Store from the authentication schemes that refer to it.

OAM-18012
Exception while processing the User Identity Store properties.

Category:
Other

Cause:
An internal error occurred, Unknown type found while processing.

Action:
For more details, start foundation config logging at FINE level.

OAM-18013
Exception while processing the User Identity Store properties.

Category:
Other

Cause:
An internal error occurred, type found as NULL while processing.

Action:
For more details, start foundation config logging at FINE level.

OAM-18014
Validation Failure - NULL Value passed for property "{0}".

Category:
Other

Cause:
Value found as NULL for a property.

Action:
Rerun with the value of property set.

OAM-18015
Server Configuration is not valid.

Category:
Other

Cause:
The server configuration was missing, or was invalid.

Action:
Verify the server configuration.

OAM-18016
Cannot initialize the Data Sources Manager.

Category:
Other

Cause:
Configuration store instance found null.

Action:
For more details, start logging at the FINE level.

OAM-18017
Cannot initialize the Authentication Modules Manager.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-18018
Cannot initialize the Server Manager.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start logging at the FINE level.

OAM-18019
Create : {0} : paramList=[{1}].

Category:
Other

Cause:

Action:

OAM-18020
Created : {0} : {1}.

Category:
Other

Cause:

Action:

OAM-18021
Modify : {0} : Existing=[{1}] : New=[{2}].

Category:
Other

Cause:

Action:

OAM-18022
Modified to : {0} : {1}.

Category:
Other

Cause:

Action:

OAM-18023
Delete : {0} : name="{1}".

Category:
Other

Cause:

Action:

OAM-18024
Deleted : {0} : name="{1}".

Category:
Other

Cause:

Action:

OAM-18025
Read : {0} : name="{1}".

Category:
Other

Cause:

Action:

OAM-18026
After Read : {0} : {1}.

Category:
Other

Cause:

Action:

OAM-18027
Read All : {0}.

Category:
Other

Cause:

Action:

OAM-18028
After Read All : {0} : list is : {1}.

Category:
Other

Cause:

Action:

OAM-18029
Validation Failure : "{0}" attributes missing in User Identity Store.

Category:
Other

Cause:
The required attributes were not present in the user identity store.

Action:
Add the attributes to the user identity store and rerun the operation.

OAM-18030
Validation Failure : "{0}" attributes missing in OAM Server Instance.

Category:
Other

Cause:
The required attributes were not specified for the server instance.

Action:
Add the attributes to the server instance and rerun the operation.

OAM-18031
Validation Failure : "{0}" attributes missing in {1} Authentication Module.

Category:
Other

Cause:
The required attributes were not specified for the authentication module.

Action:
Add the attributes to the authentication module and rerun the operation.

OAM-18032
Validation Failure - Object not found for deletion.

Category:
Other

Cause:
The object supplied for deletion has been deleted, or does not exist.

Action:
Use the correct data and rerun the operation.

OAM-18033
Validation Failure : {0} Module cannot be deleted. (Referred in Scheme).

Category:
Other

Cause:
The module was being referred to in a scheme.

Action:
Remove the reference from the scheme and then delete the module.

OAM-18034
Authentication module configuration is not valid.

Category:
Other

Cause:
The authentication module configuration was missing, or was invalid.

Action:
Verify the authentication module configuration.

OAM-18035
Validation Failure - a server Instance named "{0}" already exists.

Category:
Other

Cause:
Same name used for creating a new server instance.

Action:

OAM-18036
OAM Server name passed as NULL during oam server update operation.

Category:
Other

Cause:
An internal error occurred.

Action:

OAM-18037
OAM Server id passed as NULL during oam server update operation.

Category:
Other

Cause:
User Identity Store name passed to read operation was null.

Action:

OAM-18038
The response cookie configuration for update is invalid.

Category:
Other

Cause:
Invalid OSSO Proxy configuration found during configuration update.

Action:
Check the parameter passed during OSSO-Proxy configuration update.

OAM-18039
The global response cookie configuration cannot be deleted.

Category:
Other

Cause:
The global OSSO response cookie configuration delete is not allowed.

Action:
Check the parameter passed during OSSO-Proxy configuration update.

OAM-18040
Error while reading {0} Authentication Module Configuration.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18041
Error while reading OAM Server Instance Configuration.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18042
The Unique ID for server is null.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18043
The OAM server is null.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18044
Error while reading {0} OAM Server Instance Configuration.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18045
OAM Server name passsed as NULL during server read operation.

Category:
Other

Cause:
User Identity Store name passsed to read operation was null.

Action:
Rerun with actual object.

OAM-18046
OAM Server ID passsed as blank during server read operation.

Category:
Other

Cause:
User Identity Store ID passsed to read operation was blank.

Action:
Rerun with a valid ID.

OAM-18047
Error while reading Kerberos Authentication Module Configuration.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18048
The Unique Authn module ID is null.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18049
The authn module is null.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18050
Error while reading LDAP Authentication Module Configuration.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18051
Error while reading X509 Authentication Module Configuration.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18052
Error while reading DAP Authentication Module Configuration.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18053
Internal error occurred while reading {0} Authentication module.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18054
An Authentication Module with name {0} already exists, please specify another name.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18055
Internal error occurred while reading OAM Server {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18056
Internal error occurred while reading Load Balancing Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18057
Internal error occurred while updating Load Balancing Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18058
Internal error occurred while reading SSO Engine Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18059
Internal error occurred while updating SSO Engine Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18060
Internal error occurred while reading Coherence Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18061
Internal error occurred while updating Coherence Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18062
Internal error occurred while reading Session Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18063
Internal error occurred while updating Session Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18064
Internal error occurred while reading Access Protocol Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18065
Internal error occurred while updating Access Protocol Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18066
Internal error occurred while reading Policy Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18067
Internal error occurred while updating Policy Settings.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18068
Invalid Orchestration Strategy.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18069
Error saving Custom Authentication Module.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18070
Custom Authentication module is unavailable.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18071
Error deleting Custom Authentication Module.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18072
Custom Authentication module already exists.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18073
The specified ID Store is not a System Store.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-18074
Delete operation on System Identity Store is not allowed.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start foundation config logging at FINE level.

OAM-20001
Deleted application domain {0}.

Category:
Other

Cause:

Action:

OAM-20002
Duplicated application domain {0}.

Category:
Other

Cause:

Action:

OAM-20003
Saved authentication scheme {0}.

Category:
Other

Cause:

Action:

OAM-20004
Deleted authentication scheme {0}.

Category:
Other

Cause:

Action:

OAM-20005
Duplicated authentication scheme {0}.

Category:
Other

Cause:

Action:

OAM-20006
Button with id {0} is disabled {1}

Category:
Other

Cause:

Action:

OAM-20007
Set authentication scheme {0} as the default scheme.

Category:
Other

Cause:

Action:

OAM-20008
Set {0} as the default authentication scheme.

Category:
Other

Cause:

Action:

OAM-20009
Saved host identifier {0}.

Category:
Other

Cause:

Action:

OAM-20010
Deleted host identifier {0}.

Category:
Other

Cause:

Action:

OAM-20011
Duplicated host identifier{0}.

Category:
Other

Cause:

Action:

OAM-20012
Deleted host identifier entry with key {0}

Category:
Other

Cause:

Action:

OAM-20013
Saved resource {0}.

Category:
Other

Cause:

Action:

OAM-20014
Deleted resource {0}.

Category:
Other

Cause:

Action:

OAM-20015
Duplicated resource {0}.

Category:
Other

Cause:

Action:

OAM-20016
Saved authentication policy {0}.

Category:
Other

Cause:

Action:

OAM-20017
Deleted authentication policy {0}.

Category:
Other

Cause:

Action:

OAM-20018
Duplicated authentication policy {0}.

Category:
Other

Cause:

Action:

OAM-20019
Saved authorization policy {0}.

Category:
Other

Cause:

Action:

OAM-20020
Deleted authorization policy {0}.

Category:
Other

Cause:

Action:

OAM-20021
Duplicated authorization policy {0}.

Category:
Other

Cause:

Action:

OAM-20022
Saving authentication policy response {0}, {1}, {2}.

Category:
Other

Cause:

Action:

OAM-20023
Saved authentication policy response {0}.

Category:
Other

Cause:

Action:

OAM-20024
Deleted authentication policy response row with key {0}.

Category:
Other

Cause:

Action:

OAM-20025
Deleted authentication policy response {0}.

Category:
Other

Cause:

Action:

OAM-20026
Saved authentication policy resource {0}.

Category:
Other

Cause:

Action:

OAM-20027
Deleted authentication policy resource with key {0}.

Category:
Other

Cause:

Action:

OAM-20028
Deleted authentication policy resource {0}.

Category:
Other

Cause:

Action:

OAM-20029
Saving authorization policy response {0}, {1}, {2}.

Category:
Other

Cause:

Action:

OAM-20030
Saved authorization policy response {0}.

Category:
Other

Cause:

Action:

OAM-20031
Deleted authorization policy response with key {0}.

Category:
Other

Cause:

Action:

OAM-20032
Deleted authorization policy response {0}.

Category:
Other

Cause:

Action:

OAM-20033
Saved authorization policy resource {0}.

Category:
Other

Cause:

Action:

OAM-20034
Deleted authorization policy resource with key {0}.

Category:
Other

Cause:

Action:

OAM-20035
Deleted authorization policy resource {0}.

Category:
Other

Cause:

Action:

OAM-20036
Added {0}:{1}:{2} constraint.

Category:
Other

Cause:

Action:

OAM-20037
Added constraint {0}.

Category:
Other

Cause:

Action:

OAM-20038
Saved constraint {0}.

Category:
Other

Cause:

Action:

OAM-20039
Deleted constraint with key {0}.

Category:
Other

Cause:

Action:

OAM-20040
Deleted constraint {0}.

Category:
Other

Cause:

Action:

OAM-20041
Fetching details for master constraint {0}:{1}:{2}.

Category:
Other

Cause:

Action:

OAM-20042
Saved details for temporal constraint {0}.

Category:
Other

Cause:

Action:

OAM-20043
Cancelled detail changes for temporal constraint {0}.

Category:
Other

Cause:

Action:

OAM-20044
Saved details for ip4 constraint {0}.

Category:
Other

Cause:

Action:

OAM-20045
Cancelled detail changes for ip4 constraint {0}.

Category:
Other

Cause:

Action:

OAM-20046
Saved details for identity constraint {0}.

Category:
Other

Cause:

Action:

OAM-20047
Cancelled detail changes for identity constraint {0}.

Category:
Other

Cause:

Action:

OAM-20048
Added {0}:{1} under identity constraint.

Category:
Other

Cause:

Action:

OAM-20049
Deleted key {0}:{1} under identity constraint.

Category:
Other

Cause:

Action:

OAM-20050
Deleted {0}:{1} under identity constraint.

Category:
Other

Cause:

Action:

OAM-20051
Searching for {0}:{1}.

Category:
Other

Cause:

Action:

OAM-20052
Saved component {0}:{1}.

Category:
Other

Cause:

Action:

OAM-20053
Created component {0}:{1}.

Category:
Other

Cause:

Action:

OAM-20054
Duplicated component {0}:{1}.

Category:
Other

Cause:

Action:

OAM-20055
Deleted component {0}:{1}.

Category:
Other

Cause:

Action:

OAM-20056
Recording action:{0}, child node:{1}, appdomain name:{2}.

Category:
Other

Cause:

Action:

OAM-20057
Cancelled application domain {0}.

Category:
Other

Cause:

Action:

OAM-20058
Cancelled authentication scheme {0}.

Category:
Other

Cause:

Action:

OAM-20059
Cancelled host identifier {0}.

Category:
Other

Cause:

Action:

OAM-20060
Cancelled resource {0}.

Category:
Other

Cause:

Action:

OAM-20061
Cancelled authentication policy {0}.

Category:
Other

Cause:

Action:

OAM-20062
Cancelled authorization policy {0}.

Category:
Other

Cause:

Action:

OAM-20063
Successfully saved application domain {0}.

Category:
Other

Cause:

Action:

OAM-20100
Cannot save application domain {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20101
Cannot delete application domain {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20102
Cannot duplicate application domain{0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20103
Cannot save authentication scheme {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20104
Cannot delete authentication scheme {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20105
Cannot duplicate authentication scheme {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20106
Cannot set {0} as the default authentication scheme.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20107
Cannot save host identifier {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20108
Cannot delete host identifier {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20109
Cannot duplicate host identifier {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20110
Cannot save resource {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20111
Cannot delete resource {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20112
Cannot duplicate resource {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20113
Cannot save authentication policy {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20114
Cannot duplicate authentication policy {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20115
Cannot delete authentication policy {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20116
Cannot save authorization policy {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20117
Cannot duplicate authorization policy {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20118
Cannot delete authorization policy {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20119
Cannot initialize authentication policy response.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20120
Cannot save authentication policy response {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20121
Cannot delete authentication policy response {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20122
Cannot save authentication policy resource {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20123
Cannot delete authentication policy resource {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20124
Cannot initialize authorization policy response.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20125
Cannot save authorization policy response {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20126
Cannot delete authorization policy response {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20127
Cannot save authorization policy resource {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20128
Cannot delete authorization policy resource {0}.

Category:
Other

Cause:
AuthzPolicyResource delete failed.

Action:
AuthzPolicyResource delete failed.

OAM-20129
Cannot save constraint {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20130
Cannot delete constraint {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20131
Cannot save details for temporal constraint {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20132
Cannot cancel detail changes for temporal constraint {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20133
Cannot save details for ip4 constraint {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20134
Cannot cancel detail changes for ip4 constraint {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20135
Cannot save details for identity constraint {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20136
Cannot cancel detail changes for identity constraint {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20137
Cannot save details for identity constraint {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20138
Cannot delete details under identity constraint {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20139
Error occurred while searching for {0}:{1}.

Category:
Other

Cause:

Action:

OAM-20140
Cannot save component {0}:{1}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20141
Cannot create component {0}:{1}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20142
Cannot duplicate component {0}:{1}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20143
Cannot delete component {0}:{1}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20144
Cannot cancel action for component {0}:{1}.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details,start logging at the FINE level.

OAM-20145
Cannot cancel application domain {0}.

Category:
Other

Cause:

Action:

OAM-20146
Cannot cancel authentication scheme {0}.

Category:
Other

Cause:

Action:

OAM-20147
Cannot cancel host identifier {0}.

Category:
Other

Cause:

Action:

OAM-20148
Cannot cancel resource {0}.

Category:
Other

Cause:

Action:

OAM-20149
Cannot cancel authentication policy {0}.

Category:
Other

Cause:

Action:

OAM-20150
Cannot cancel authorization policy {0}.

Category:
Other

Cause:

Action:

OAM-21000
Create : {0} : paramList=[{1}].

Category:
Other

Cause:

Action:

OAM-21001
Created {0} : {1}.

Category:
Other

Cause:

Action:

OAM-21002
Modify : {0} : Existing=[{1}] : New=[{2}].

Category:
Other

Cause:

Action:

OAM-21003
Modified to : {0} : {1}.

Category:
Other

Cause:

Action:

OAM-21004
Exception encountered while parsing start date of OSSO Agent!

Category:
Other

Cause:
An internal exception occurred.

Action:
For more details, start oam console logging at FINE level.

OAM-21005
NULL Refresh Call back.

Category:
Other

Cause:
Refresh Call back object for refreshing LHS tree found NULL.

Action:
For more details, start oam console logging at FINE level.

OAM-21006
NULL Registration Server Controller.

Category:
Other

Cause:
Registration Server Controller found NULL.

Action:
For more details, start oam console logging at FINE level.

OAM-22001
Error occured during cleanUpPolicy : {0}

Category:
Other

Cause:
Error occured during cleanUpPolicy.

Action:
Check the OAM t2p logs.

OAM-22002
Error occured during cleanUpApplicationDomains : {0}

Category:
Other

Cause:
Error occured during cleanUpApplicationDomains.

Action:
Check the OAM t2p logs.

OAM-22003
Error occured during initialization : {0}

Category:
Other

Cause:
Error occured during initialization.

Action:
Check the OAM t2p logs.

OAM-22004
Error occured during copying HostIdentifiers : {0}

Category:
Other

Cause:
Error occured during copying HostIdentifiers.

Action:
Check the OAM t2p logs.

OAM-22005
Error occured during copying policy changes : {0}

Category:
Other

Cause:
Error occured during copying policy changes.

Action:
Check the OAM t2p logs.

OAM-22006
Fetched partners from OAM server.

Category:
Other

Cause:
None

Action:
None

OAM-22007
Applied partners to OAM server.

Category:
Other

Cause:
None

Action:
None

OAM-22008
Switching off policy distribution.

Category:
Other

Cause:
None

Action:
None

OAM-22009
Cleaned up policy file : {0}.

Category:
Other

Cause:
None

Action:
None

OAM-22010
Copied policy changes to the intermediate file.

Category:
Other

Cause:
None

Action:
None

OAM-22011
Switching on policy distribution.

Category:
Other

Cause:
None

Action:
None

OAM-22012
Copied policy changes from the intermediate file.

Category:
Other

Cause:
None

Action:
None

OAM-22013
Added host {0}:{1} to {2}.

Category:
Other

Cause:
None

Action:
None

OAM-22014
Removed host {0}:{1} from {2}.

Category:
Other

Cause:
None

Action:
None

OAM-22015
Removed resource {0} and policies using this resource from application domain {1}.

Category:
Other

Cause:
None

Action:
None

OAM-22016
Error occured during creating application domain : {0}

Category:
Other

Cause:
Error occured during creating application domain.

Action:
Check the OAM t2p logs.

OAM-22017
Error occured during removing resource : {0}

Category:
Other

Cause:
Error occured during creating application domain.

Action:
Check the OAM t2p logs.

OAM-22018
Error occured during decrypting key : {0}

Category:
Other

Cause:
Error occured during decrypting key.

Action:
Check the OAM t2p logs.

OAM-22019
Error occured during encrypting key : {0}

Category:
Other

Cause:
Error occured during encrypting key.

Action:
Check the OAM t2p logs.

OAM-22020
Authentication module {0} is not present in the production system. Using the authentication module {1} to create the authentication scheme {2}

Category:
Other

Cause:
Authentication scheme cannot be created.

Action:
Check the OAM t2p logs.

OAM-22021
Intermediate OAM file was not found in the location {0}. Creating the intermediate file.

Category:
Other

Cause:
None

Action:
None

OAM-22022
Error while creating the intermediate OAM policy file : {0}

Category:
Other

Cause:
Intermediate file cannot be created.

Action:
Check the OAM t2p logs.

OAM-22023
Error while setting the default authentication scheme: {0}

Category:
Other

Cause:
Default authentication scheme cannot be created.

Action:
Check the OAM t2p logs.

OAM-22024
Error while fetching the Partners: {0}

Category:
Other

Cause:
Error while fetching the Partners.

Action:
Check the OAM t2p logs.

OAM-22025
Error while writing Partners into a intermediate file: {0}

Category:
Other

Cause:
Error while writing Partners into a intermediate file.

Action:
Check the OAM t2p logs.

OAM-22026
Error while applying Partners: {0}

Category:
Other

Cause:
Error while applying Partners.

Action:
Check the OAM t2p logs.

OAM-22027
Error while exporting Partners: {0}

Category:
Other

Cause:
Error while exporting Partners.

Action:
Check the OAM t2p logs.

OAM-22028
Error while applying the Policy Configuration to PS1 instance

Category:
Other

Cause:
Intermediate file cannot be created.

Action:
Check the OAM t2p logs.

OAM-22029
Error while applying the System Configuration to PS1 instance

Category:
Other

Cause:
Intermediate file cannot be created.

Action:
Check the OAM t2p logs.

OAM-22030
Error while applying the KeyStore Configuration to PS1 instance

Category:
Other

Cause:
Intermediate file cannot be created.

Action:
Check the OAM t2p logs.

OAM-22031
Error while loading the given class dynamically for transformations

Category:
Other

Cause:
Error in loading the given class dynamically.

Action:
Check the OAM t2p logs.

OAM-22032
Loaded class is not the valid instance of a specific interface

Category:
Other

Cause:
Loaded class is not a valid instance of given interface

Action:
Check the OAM t2p logs.

OAM-22033
Transformation class is not found

Category:
Other

Cause:
Loaded class is not a valid instance of given interface

Action:
Check the OAM t2p logs.

OAM-22034
Error creating file ouput stream.

Category:
Other

Cause:
Could not create output stream.

Action:
Check the OAM t2p logs.

OAM-22035
Error creating/writing to object output stream.

Category:
Other

Cause:
Could not create object output stream.

Action:
Check the OAM t2p logs.

OAM-22036
Error closing output stream.

Category:
Other

Cause:
Could not close output stream.

Action:
Check the OAM t2p logs.

OAM-22037
Error creating file input stream.

Category:
Other

Cause:
Could not open file input stream

Action:
Check the OAM t2p logs.

OAM-22038
Error creating object input stream.

Category:
Other

Cause:
could not open object input stream

Action:
Check the OAM t2p logs.

OAM-22039
Error deserializing object.

Category:
Other

Cause:
Could not de-serialize patrner object

Action:
Check the OAM t2p logs.

OAM-22040
Error reading from object Stream.

Category:
Other

Cause:
Could not read from object stream

Action:
Check the OAM t2p logs.

OAM-22041
Error occurred during partner re-registration

Category:
Other

Cause:
an error occurred during partner re-registration

Action:
Check the OAM t2p logs.

OAM-22042
Error while migrating partners information

Category:
Other

Cause:
Error while migrating partners

Action:
Check the OAM t2p logs.

OAM-22043
Error while getting migrating partners information

Category:
Other

Cause:
Error while getting migrating partners information

Action:
Check the OAM t2p logs.

OAM-22044
Error while writing migrating partners information

Category:
Other

Cause:
Error while writing migrating partners information

Action:
Check the OAM t2p logs.

OAM-22045
Error while certificate migration

Category:
Other

Cause:
Error while certificate migration

Action:
Check the OAM t2p logs.

OAM-22046
Export policy file with name {0} already exists.

Category:
Other

Cause:
A file already exists with the same name as policy export file.

Action:
Ensure the no file exists with same name as policy export file.

OAM-24001
Unable to execute the WLST Command

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24002
OSSO-Proxy configuration update operation failed.

Category:
Other

Cause:
The OSSO-Proxy configuration update in OAM system config failed.

Action:
Enable detailed logging for details of the failure.

OAM-24003
Given ID Store name doesn't exist

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24004
No properties file provided

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24005
Failed to create user id store in online mode

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24006
Unable to fetch LDAP Properties file

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24007
Value of Cookie passed is invalid

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24008
Error while closing the streams

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24009
Error while copying files

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24010
Error while wrapping and unwrapping files

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24011
Map retrieved from backend is null

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24012
One of the mandatory values is null

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24013
Unknown Version

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24014
LDAP Provider was invalid : {0}

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24015
Edit command parameter value is invalid

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24016
Unable to fetch the Server details

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24021
TAP Redirect URL is invalid, Registration failed.

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24022
Unable to contact the TAP Redirect URL, Registration failed.

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24023
TAP Redirect URL is null, Registration failed.

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24024
Exception fetching the authentication scheme, Registration failed.

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24025
TAP Key generation error.

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24026
TAP Key store generation error.

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24027
TAP Partner Registration Successful.

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24028
Error while retrieving keystore password using MBean connection.

Category:
Other

Cause:
Error while retrieving keystore password using MBean connection.

Action:
Error while retrieving keystore password using MBean connection.

OAM-24029
One of the mandatory values is null

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24030
Closing the stream failed.

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24031
Error in wrap and unwrap.

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24032
Osso proxy cookie value is empty.

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24033
Cannot find LdapProperties file

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-24034
TAP Scheme not available to update TAPRedirect URL

Category:
Other

Cause:
The WLST command execution failed.

Action:
For more details, start logging at the FINE level.

OAM-25001
SSO only mode is not matching true.

Category:
Other

Cause:
Validation error

Action:
Validation error

OAM-25003
Wrong OAM Access Server host name.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25004
Wrong OAM Access Server port.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25005
Wrong OAM second access server host.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25006
Wrong OAM second access server port.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25007
Wrong OIM host name.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25008
Wrong OIM port.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25009
Wrong OIM URL Protocol.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25010
Wrong IDStore host name.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25011
Wrong IDStore port.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25012
Wrong IDSTore SSL flag true.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25013
Identity service not enabled.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25014
Identity service enabled.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25015
SSO only mode is not matching false.

Category:
Other

Cause:
Validation error

Action:
Validation error

OAM-25016
Wrong IDSTore SSL flag false.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25017
Invalid administrator user name.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25018
Invalid administrator user name/password. Login failed.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25019
Invalid administrator user roles.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25020
Error validating administrator user.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25021
Error in certificate validation of connecting url.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25022
Bad SSL Key from the contacting server.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25031
Invalid global WebGate pass phrase.

Category:
Other

Cause:
Validation error

Action:
None

OAM-25051
Error in retrieving default authentication scheme.

Category:
Other

Cause:
Invalid Name

Action:
None

OAM-25052
Class name is not passed.

Category:
Other

Cause:
Invalid Name

Action:
None

OAM-25053
Class name not found in the server mapper.

Category:
Other

Cause:
Invalid Name

Action:
None

OAM-25054
Error while executing method in test class.

Category:
Other

Cause:
Invalid Name

Action:
None

OAM-25055
Mapper does not have method.

Category:
Other

Cause:
Invalid Name

Action:
None

OAM-25056
Either cache service is down, or expected to find at least 2 cache nodes and did not. {0} cache nodes running.

Category:
Other

Cause:
Cache servers are not running.

Action:
Restart the admin server.

OAM-25058
User {0} is not authorized to invoke operation on the Oracle Access Management MBeans.

Category:
Other

Cause:
The user does not have the privileges to access the MBeans.

Action:
Verify the System Identity Store configuration to ensure the correct privileges are set.

OAM-30001
Invalid user credentials. Registration failed. Try again after providing valid credentials.

Category:
Other

Cause:
Username/password credentials provided are invalid.

Action:
Try again after providing valid credentials.

OAM-30002
User does not belong to the group that is authorized to perform registration. Registration failed. Try again after verifying the user's group.

Category:
Other

Cause:
User does not have a valid role to perform remote registration.

Action:
Try again after verifying the user's role.

OAM-30003
Agent name "{0}" already exists. Existing agent profile information from the server will be used to generate artifacts.

Category:
Other

Cause:
Agent name is not unique, it already exists.

Action:

OAM-30004
Agent type is unrecognized or is invalid for the operation being performed: "{0}". Registration failed.

Category:
Other

Cause:
An internal error occurred due to unknown request type.

Action:
For more details, start remote registration logging at FINE level.

OAM-30005
Output folder could not be created in the server domain home. Registration failed.

Category:
Other

Cause:
An internal error occurred as output folder could not be created in the server location.

Action:
Verify permissions to create the folder.

OAM-30006
Exception encountered while creating one or more of the output artifacts : {0}.

Category:
Other

Cause:
An internal error occurred while creating response file.

Action:
For more details, start remote registration logging at FINE level.

OAM-30007
Exception encountered while validating using User/Role API : {0}. The exception trace is : {1}

Category:
Other

Cause:
An internal error occurred.

Action:
Please verify credentials/role and try again.

OAM-30008
User/Role API not available or could not be initialized. Registration failed.

Category:
Other

Cause:
An internal error occurred.

Action:
For more details, start remote registration logging at FINE level.

OAM-30009
Application domain with the same name already exists. Registration failed. Try again after providing a unique application domain(agent name).

Category:
Other

Cause:
Application domain name is not unique.

Action:
Try again after providing a unique application domain(agent name).

OAM-30010
Anonymous authentication scheme does not exist so initial public authn policy cannot be created. Registration failed.

Category:
Other

Cause:
An internal error occurred as anonymous scheme does not exist.

Action:
For more details, start remote registration logging at FINE level.

OAM-30011
The host:port is not unique. A different host identifier with name : "{0}" already exists for this host:port.

Category:
Other

Cause:
AgentBaseUrl specified is already registered under a different hostidentifier name.

Action:
Try again after entering a unique agentBaseUrl value.

OAM-30012
Error in encrypting the secret key. Registration failed.

Category:
Other

Cause:
An internal error occurred. Error in encrypting the secretkey.

Action:
Try again after checking server configuration.

OAM-30013
Error in generating the secret key. Registration failed: {0}

Category:
Other

Cause:
An internal error occurred. Error in creating the secretkey.

Action:

OAM-30014
GlobalPassphrase retrieved from server configuration is null. Registration failed.

Category:
Other

Cause:
An internal error occurred. Error in retrieving globalPassphrase.

Action:

OAM-30015
Error in decrypting the encrypted globalPassphrase. Registration failed.

Category:
Other

Cause:
An internal error occurred. Error in decrypting the retrieved globalPassphrase.

Action:

OAM-30016
Error in obfuscating the decrypted globalPassphrase. Registration failed.

Category:
Other

Cause:
An internal error occurred. Error in obfuscating the decrypted globalPassphrase.

Action:

OAM-30017
Internal error occurred. One of the mandatory response parameters is null. Registration failed.

Category:
Other

Cause:
An internal error occurred. One or more of the mandatory response fields is empty.

Action:

OAM-30018
Internal error occurred. No response generated, due to either bad input or backend failure. See log file for details.

Category:
Other

Cause:
An internal error occurred. No response generated due to backend failure.

Action:
See log file for details.

OAM-30019
Exception encountered either while creating or writing to the native config file : {0}

Category:
Other

Cause:
An internal error occurred during creation of native config file

Action:

OAM-30020
Exception encountered while writing to the output password file : {0}

Category:
Other

Cause:
An internal error occurred during creation of output password.xml file

Action:

OAM-30021
Error in obfuscating the OSSO agent's output config file (osso.conf). Registration failed.

Category:
Other

Cause:
An internal error occurred. Error in obfuscating the created osso.conf config file.

Action:

OAM-30022
Error in creating the credential store (wallet) : {0}

Category:
Other

Cause:
An internal error occurred. Error in creating the creating the credential store (wallet).

Action:

OAM-30023
Error in storing the secretKey in the credential store (wallet): {0}

Category:
Other

Cause:
An internal error occurred. Error in storing the secretkey in the credential store (wallet).

Action:

OAM-30024
Error occurred while parsing the XML file. Error message is : "{0}" at column number : "{1}" and at line number : "{2}"

Category:
Other

Cause:
The XML file provided is invalid or not well-formed.

Action:
Try again after verifying syntax and well-formedness of the XML as per the schema.

OAM-30025
Malformed registration request xml string : "{0}" - {1}

Category:
Other

Cause:
The XML request string generated is malformed.

Action:
Internal error during parsing. Check the input request xml and try again.

OAM-30026
{0}

Category:
Other

Cause:

Action:

OAM-30027
Error in unmarshalling operation : {0}

Category:
Other

Cause:
Error in unmarshalling the XML data.

Action:
Try again after verifying syntax and well-formedness of the XML as per the schema.

OAM-30028
Error in setting the validation schema : {0}

Category:
Other

Cause:
Error in setting the validation schema

Action:

OAM-30029
Error in setting the validation event handler : {0}

Category:
Other

Cause:
Error in setting the validation event handler

Action:

OAM-30030
Error in marshalling operation : {0}

Category:
Other

Cause:
Error in marshalling the data.

Action:

OAM-30031
The character encoding being used is not supported : {0}

Category:
Other

Cause:
Internal error. Unsuppported character encoding being used.

Action:

OAM-30032
Exception encountered while writing to the certificate file : "{0}". Error message is: {1}

Category:
Other

Cause:
An internal error occurred during creation of output password.xml file

Action:

OAM-30033
Certificates could not be retrieved from the server location. Registration failed: {0}

Category:
Other

Cause:
An internal error occurred. Error in retrieving the certificates.

Action:

OAM-30034
Error while reading the certificate file stream. Registration failed: {0}

Category:
Other

Cause:
An internal error occurred. Error in retrieving the certificates.

Action:

OAM-30035
Server instance is not running for the security mode specified: "{0}".

Category:
Other

Cause:
Server instance not running for the security mode specified.

Action:

OAM-30036
Internal server error. No server instances are running.

Category:
Other

Cause:
Internal server error occurred. No server instances exist.

Action:

OAM-30037
Server instance is not running for the security mode specified: "{0}". Try again using a different security mode.

Category:
Other

Cause:
Server instance not running for the security mode specified

Action:
Try again using a different security mode

OAM-30038
Internal server error. There are no server instances running. Registration failed. Please try again later.

Category:
Other

Cause:

Action:

OAM-30039
Default security mode picked up for agent is: "{0}".

Category:
Other

Cause:

Action:

OAM-30040
Could not retrieve the timeout cookie name and timeout cookie key information from the server configuration. Registration failed.

Category:
Other

Cause:
An internal error occurred. Error in retrieving timeout cookie name and timeout cookie key for the agent.

Action:

OAM-30041
Error while generating the cipher key or mask for the agent. Registration failed: {0}

Category:
Other

Cause:
An internal error occurred. Error in generating the cipher key or mask for the agent.

Action:

OAM-30042
Error in decrypting the secret key while passing back in the response. Registration failed.

Category:
Other

Cause:
An internal error occurred. Error in decrypting the secretkey while passing back in the response.

Action:

OAM-30043
Agent type in the request is either null or unidentified. Please try again after verifying the agent type.

Category:
Other

Cause:
Agent type that is passed in the request object is invalid.

Action:
Try again after checking the agent type that is specified.

OAM-30044
Internal error while encrypting/obfuscating the password. Registration failed: {0}

Category:
Other

Cause:
An internal error occurred. Error in encrypting/obfuscating the password.

Action:

OAM-30045
The hostIdentifier string: "{0}" has already been added to an existing hostIdentifier called: "{1}". Try again after deleting the host entry from the existing hostIdentifier or registering with a new hostIdentifier name.

Category:
Other

Cause:
The hostIdentifier string specified is already registered under a different hostidentifier name.

Action:
Try again after deleting the host entry from the existing hostIdentifier or registering with a new hostIdentifier name.

OAM-30046
{0} mode failed. Agent does not exist.

Category:
Other

Cause:
Agent is not found.

Action:

OAM-30047
Agent is found, but application domain does not exist. Agent could be in different application domain.

Category:
Other

Cause:
The Application Domain is not found.

Action:
For validation, application domain name is agent name.

OAM-30048
Url is not valid. Ensure that URL is of the format http://example.domain.com:port or https://example.domain.com:port, where port number is optional.

Category:
Other

Cause:
Url is not valid.

Action:

OAM-30049
Exception encountered while creating the logout.html script file : {0}

Category:
Other

Cause:
An internal error occurred while creating the logout.html script file

Action:

OAM-30050
In DELETEMODE, agent profile deleted successfully, however, artifacts output directory was not present or could not be deleted for the agent name: "{0}" at the output folder location: "{1}". Please delete the folder manually.

Category:
Other

Cause:

Action:

OAM-30051
In DELETEMODE, agent profile and artifacts output directory was successfully deleted for the agent name: "{0}" at the server side output folder location: "{1}".

Category:
Other

Cause:

Action:

OAM-30052
Exception encountered while updating agent profile. Update of agent failed. {0}

Category:
Other

Cause:
An internal error occurred while updating agent profile

Action:

OAM-30053
Application domain does not exist. Policy update failed.

Category:
Other

Cause:
The Application Domain is not found.

Action:
Verify that the application domain you want to update exists and then try again.

OAM-30054
Host identifier does not exist or is empty. {0} mode failed.

Category:
Other

Cause:
The Hostidentifier is not found.

Action:
Verify that the hostidentifier you want to update exists and then try again.

OAM-30055
The host: "{0}" and port: "{1}" is already present under the hostIdentifier: "{2}" and was not added again.

Category:
Other

Cause:
The hostPortVariation specified is already registered under an existing hostidentifier name, so it will not be added again.

Action:

OAM-30056
Application domain already exists. policyCreate mode failed. Use policyUpdate mode to update existing application domains.

Category:
Other

Cause:
For policyCreate mode, application Domain already exists.

Action:
Try again using policyUpdate mode to update existing application domains.

OAM-30057
Create policy resource exception. {0} URI={1}

Category:
Other

Cause:
create resource failed. resouce/uri format is not valid.

Action:

OAM-30058
Agent name {0} exceeds maximum allowed length of {1} characters.

Category:
Other

Cause:
The name of the agent being created was too long.

Action:
Try again using a shorter name.

OAM-30059
The user-specified managed server name/id: "{0}" does not exist. Registration failed. Please try again after specifying valid server name.

Category:
Other

Cause:
The user-specified managed server name/id is invalid.

Action:
Try again after providing a valid server name.

OAM-30060
Internal server error. The location "{0}" is invalid or does not exist in configuration. Registration failed.

Category:
Other

Cause:
Internal server error. The specified location in the config file is invalid or not existing.

Action:

OAM-30061
isFusionAppRegistration flag was set to: "{0}" and SSOOnlyMode field was set to true.

Category:
Other

Cause:

Action:

OAM-30062
isFusionAppRegistration flag was set to: "{0}" and denyOnNotProtected field was set to false(0).

Category:
Other

Cause:

Action:

OAM-30063
Agent type mismatch: Incoming agent request is of type: "{0}" , but the existing agent profile type in the server is: "{1}". Registration failed. Please try again after using agent name of the same type.

Category:
Other

Cause:
Incoming agent type does not match with the agent type already registered in the server.

Action:
Verify that the agentName belongs to the same type and try again.

OAM-30064
Agent version mismatch: Incoming agent request is of the correct type: "{0}" , but the version is: "{1}" , while the existing agent version in the server is: "{2}". Registration failed. Please try again after using agent name of the same version.

Category:
Other

Cause:
Incoming agent type is the same, however, does not match the agent version already registered in the server.

Action:
Verify that the agentName belongs to the same version and try again.

OAM-30065
Registration failed. Error in finding or reading the template file {0} for agent:{1} of type:{2}. - {3}

Category:
Other

Cause:
An internal error occurred: the template file was not found or could not be opened.

Action:

OAM-30066
Warning: The host:port variation - {0}:{1} is not present under the hostIdentifier - {2} and so was not deleted.

Category:
Other

Cause:
The host:port variation is not present under the given hostIdentifier

Action:
Verify that the host:port variation you are passing is actually present

OAM-30067
Warning: HostIdentifier {0} cannot be empty, so added this host:port entry back to it - {1}:{2}

Category:
Other

Cause:
The hostIdentifier cannot be empty, so cannot delete all host:port entries under it

Action:
Adds the last entry being deleted back to the hostIdentifier

OAM-30068
Warning: None of the given host:port variations are present for the hostIdentifier- {0} , so nothing to delete.

Category:
Other

Cause:
None of the specified host:port variations are present under the hostIdentifier

Action:
Check the host:port variations list being passed and try again

OAM-30069
Notification: The initial protected authn policy is created.

Category:
Other

Cause:
The initial protected authn policy is created.

Action:

OAM-30070
Notification: The initial protected authz policy is created.

Category:
Other

Cause:
The initial protected authz policy is created.

Action:

OAM-30071
Notification: The public authn policy using Anonymous Scheme is created.

Category:
Other

Cause:
The public authn policy using Anonymous Scheme is created.

Action:

OAM-30072
Notification: The authn policy is updated.

Category:
Other

Cause:
The authn policy is updated.

Action:

OAM-30073
Notification: The authz policy is updated.

Category:
Other

Cause:
The authz policy is updated.

Action:

OAM-36001
Cannot obtain connection to domain MBean Server.

Category:
Other

Cause:
Console is not installed on the admin server.

Action:
Check installation and configuration of the mbeans.

OAM-36002
Cannot obtain MBean object.

Category:
Other

Cause:
MBean is not installed correctly.

Action:
Check installation and configuration of the mbeans.

OAM-36003
OAM service descriptor map: {0}

Category:
Other

Cause:

Action:

OAM-36004
Result from remove crl: {0}

Category:
Other

Cause:

Action:

OAM-36005
Result from getting all CRLs: {0}

Category:
Other

Cause:

Action:

OAM-36006
Certificate validation configuration map: {0}

Category:
Other

Cause:

Action:

OAM-36007
Deleting custom token: {0}

Category:
Other

Cause:

Action:

OAM-36008
Result from deleting custom token: {0}

Category:
Other

Cause:

Action:

OAM-36009
Error deleting custom token.

Category:
Other

Cause:
Error deleting custom token

Action:
Check if managed server is up. Check server logs. Check if custom token was already deleted by another user.

OAM-36010
Setting custom token to: {0}

Category:
Other

Cause:

Action:

OAM-36011
Result from setting custom token: {0}

Category:
Other

Cause:

Action:

OAM-36012
Error setting custom token.

Category:
Other

Cause:
Error updating custom token

Action:
Check if managed server is up. Check server logs. Check if custom token was deleted by another user.

OAM-36013
Creating custom token: {0}

Category:
Other

Cause:

Action:

OAM-36014
Result from creating custom token: {0}

Category:
Other

Cause:

Action:

OAM-36015
Error creating custom token.

Category:
Other

Cause:
Error creating custom token

Action:
Check if managed server is up. Check server logs. Check if custom token of this name already exists.

OAM-36016
Get All custom tokens

Category:
Other

Cause:

Action:

OAM-36017
Result from getting all custom tokens: {0}

Category:
Other

Cause:

Action:

OAM-36018
Error getting custom tokens

Category:
Other

Cause:
Error getting custom tokens

Action:
Check if managed server is up. Check server logs.

OAM-36019
Result from getting list of validation custom tokens: {0}

Category:
Other

Cause:

Action:

OAM-36020
Result from getting list of issuance custom tokens: {0}

Category:
Other

Cause:

Action:

OAM-36021
Result from getting all custom token names: {0}

Category:
Other

Cause:

Action:

OAM-36022
Result from getting custom token by name: {0}

Category:
Other

Cause:

Action:

OAM-36023
Result from geting all endpoints: {0}

Category:
Other

Cause:

Action:

OAM-36024
Setting endpoint to: {0}

Category:
Other

Cause:

Action:

OAM-36025
Result from setting endpoint: {0}

Category:
Other

Cause:

Action:

OAM-36026
Result from getting all endpoint names: {0}

Category:
Other

Cause:

Action:

OAM-36027
Error creating endpoint

Category:
Other

Cause:
Error creating endpoint

Action:
Check if managed server is up. Check server logs. Check if endpoint of this name already exists.

OAM-36028
Creating endpoint with name {0} and properties {1}

Category:
Other

Cause:

Action:

OAM-36029
Result from getting endpoint {0} by name {1}

Category:
Other

Cause:

Action:

OAM-36030
Error deleting endpoint.

Category:
Other

Cause:
Error deleting endpoint

Action:
Check if managed server is up. Check server logs. Check if endpoint was already deleted by another user.

OAM-36031
Deleting endpoint {0}

Category:
Other

Cause:

Action:

OAM-36032
Result from deleting endpoint {0}

Category:
Other

Cause:

Action:

OAM-36033
Result from getting keystore access template Names {0}

Category:
Other

Cause:

Action:

OAM-36034
Result from geting all keystore access templates {0}

Category:
Other

Cause:

Action:

OAM-36035
Result from setting keystore access template {0}

Category:
Other

Cause:

Action:

OAM-36036
Setting keystore access templates: {0}

Category:
Other

Cause:

Action:

OAM-36037
Error setting keystore access template {0}

Category:
Other

Cause:
Error updating keystoreaccesstemplate

Action:
Check if managed server is up. Check server logs. Check if template was deleted by another user.

OAM-36039
Result from setting keystore access template alias and pwd for alias {0} in csf: {1}

Category:
Other

Cause:

Action:

OAM-36040
Result from geting all keystore access template names {0}

Category:
Other

Cause:

Action:

OAM-36041
Setting security token service settings to {0}

Category:
Other

Cause:

Action:

OAM-36042
Result from after setting security token service settings {0}

Category:
Other

Cause:

Action:

OAM-36043
Error setting security token service settings.

Category:
Other

Cause:
Error setting security token service settings.

Action:
Check if managed server is up. Check server logs.

OAM-36044
Result from getting security token service settings {0}

Category:
Other

Cause:

Action:

OAM-36045
Result from getting global configuration {0}

Category:
Other

Cause:

Action:

OAM-36046
Result from setting global configuration {0}

Category:
Other

Cause:

Action:

OAM-36047
Setting STS global configuration properties {0}

Category:
Other

Cause:

Action:

OAM-36048
Error setting STS global configuration.

Category:
Other

Cause:
Error setting STS Global Configuraiton

Action:
Check if managed server is up. Check server logs.

OAM-36049
Error getting STS global configuration.

Category:
Other

Cause:
Error getting STS Global Configuration

Action:
Check if managed server is up. Check server logs.

OAM-36050
Result from getting server configuration {0}

Category:
Other

Cause:

Action:

OAM-36051
Result from setting server configuration {0}

Category:
Other

Cause:

Action:

OAM-36052
Setting STS server configuration properties {0}

Category:
Other

Cause:

Action:

OAM-36053
Error setting STS server configuration.

Category:
Other

Cause:
Error setting STS server configuration

Action:
Check if managed server is up. Check server logs.

OAM-36054
Error getting STS server configuration.

Category:
Other

Cause:
Error getting STS server configuration

Action:
Check if managed server is up. Check server logs.

OAM-36055
Result from creating token template {0}

Category:
Other

Cause:

Action:

OAM-36056
Creating token of type {0} with template type {1} and properties {2}

Category:
Other

Cause:

Action:

OAM-36057
Error creating token template.

Category:
Other

Cause:
Error creating template

Action:
Check if managed server is up. Check server logs. Check if template of this name already exists.

OAM-36058
Result from updating token template {0}

Category:
Other

Cause:

Action:

OAM-36059
Updating token of type {0} with template type {1} and properties {2}

Category:
Other

Cause:

Action:

OAM-36060
Error updating token template.

Category:
Other

Cause:
Error updating custom token

Action:
Check if managed server is up. Check server logs. Check if template was deleted by another user.

OAM-36061
Result from deleting token template {0}

Category:
Other

Cause:

Action:

OAM-36062
Deleting token template {0} of type {1}.

Category:
Other

Cause:

Action:

OAM-36063
Error deleting token template.

Category:
Other

Cause:
Error deleting template

Action:
Check if managed server is up. Check server logs. Check if template was already deleted by another user.

OAM-36064
Result from getting all issuance templates {0}

Category:
Other

Cause:

Action:

OAM-36065
Result from getting all validation templates {0}

Category:
Other

Cause:

Action:

OAM-36066
Result from getting all issuance template names {0}

Category:
Other

Cause:

Action:

OAM-36067
Result from getting all validation template names {0}

Category:
Other

Cause:

Action:

OAM-36068
Result from getting issuance template {0} by name: {1}

Category:
Other

Cause:

Action:

OAM-36069
Result from getting validation template {0} by name: {1}

Category:
Other

Cause:

Action:

OAM-36070
Result from add CRL: {0}

Category:
Other

Cause:

Action:

OAM-36071
Error adding CRL.

Category:
Other

Cause:
Error adding CRL

Action:
Check if managed server is up. Check server logs. Check if CRL file is valid and if it already exists.

OAM-36072
Error deleting CRL.

Category:
Other

Cause:
Error deleting CRL

Action:
Check if managed server is up. Check server logs. Check if CRL was already deleted by another user.

OAM-36073
Error getting all CRLs.

Category:
Other

Cause:
Error deleting custom token

Action:
Check if managed server is up. Check server logs. Check if CRL was already deleted by another user.

OAM-36074
handle query parameters: page (start, end) = ({0}, {1}), OrderBy = {2}, paramMap={3}

Category:
Other

Cause:

Action:

OAM-36075
Query response is empty

Category:
Other

Cause:

Action:

OAM-36076
Error query response: {0}

Category:
Other

Cause:
Error querying the server

Action:
Check if managed server is up. Check server logs.

OAM-36077
query response: {0}

Category:
Other

Cause:

Action:

OAM-36078
populating row with attribute values: {0}

Category:
Other

Cause:

Action:

OAM-36079
doDML operation: {0}

Category:
Other

Cause:

Action:

OAM-36080
isCreateLike: {0}

Category:
Other

Cause:

Action:

OAM-36081
parameter {0} not found

Category:
Other

Cause:

Action:

OAM-36082
null row data passed to populate attribute

Category:
Other

Cause:

Action:

OAM-36083
Result from creating partner profile {0}

Category:
Other

Cause:

Action:

OAM-36084
Creating partner profile of type {0} with properties {1}

Category:
Other

Cause:

Action:

OAM-36085
Error creating partner profile

Category:
Other

Cause:
Error creating partner profile

Action:
Check if managed server is up. Check server logs. Check if partner profile of this name already exists.

OAM-36086
Result from updating partner profile {0}

Category:
Other

Cause:

Action:

OAM-36087
Updating partner profile of type{0} with properties {1}

Category:
Other

Cause:

Action:

OAM-36088
Error updating partner profile

Category:
Other

Cause:
Error updating partner profile

Action:
Check if managed server is up. Check server logs. Check if partner profile was deleted by another user.

OAM-36089
Result from deleting partner profile {0}

Category:
Other

Cause:

Action:

OAM-36090
Deleting partner profile {0} of type {1}

Category:
Other

Cause:

Action:

OAM-36091
Error deleting partner profile

Category:
Other

Cause:
Error deleting partner profile

Action:
Check if managed server is up. Check server logs. Check if partner profile was already deleted by another user.

OAM-36092
Result from getting all partner profiles {0} of Type: {1}

Category:
Other

Cause:

Action:

OAM-36093
Result from creating partner {0}

Category:
Other

Cause:

Action:

OAM-36094
Creating partner of type {0} with properties {1}

Category:
Other

Cause:

Action:

OAM-36095
Error creating partner

Category:
Other

Cause:
Error creating partner

Action:
Check if managed server is up. Check server logs. Check if partner of this name already exists.

OAM-36096
Result from updating partner {0}

Category:
Other

Cause:

Action:

OAM-36097
Updating partner of type {0} with properties {1}

Category:
Other

Cause:

Action:

OAM-36098
Error updating partner

Category:
Other

Cause:
Error updating partner

Action:
Check if managed server is up. Check server logs. Check if this partner was deleted by another user.

OAM-36099
Result from deleting partner {0}

Category:
Other

Cause:

Action:

OAM-36100
Deleting partner {0} of type {1}

Category:
Other

Cause:

Action:

OAM-36101
Error deleting partner

Category:
Other

Cause:
Error deleting partner

Action:
Check if managed server is up. Check server logs. Check if partner was already deleted by another user.

OAM-36102
Result from getting all partners {0} of Type: {1}

Category:
Other

Cause:

Action:

OAM-36103
Result from getting WSS validation template names {0}

Category:
Other

Cause:

Action:

OAM-36104
Result from getting partner profile: {0} by name: {1}

Category:
Other

Cause:

Action:

OAM-36105
Result from getting partner: {0} by name: {1}

Category:
Other

Cause:

Action:

21
ODI-1100 to ODI-999999

ODI-1100
Agent {0} successfully cleaned up {1} stale sessions from work repository {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1101
Agent {0} successfully completed session {1} ({2}) (for scenario {3}) on {4} using context {5} with statistics: Rows {6} Inserts {7} Updates {8} Deletes {9} Errors {10}.

Category:
Other

Cause:
null

Action:
null

ODI-1102
Agent {0} successfully completed session {1} ({2}) on {3} using context {4} with statistics: Rows {5} Inserts {6} Updates {7} Deletes {8} Errors {9}.

Category:
Other

Cause:
null

Action:
null

ODI-1103
Agent {0} successfully completed step {1} in session {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1104
Agent {0} successfully connected to master repository using {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1105
Agent {0} successfully connected to work repository {1} using {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1106
Agent {0} created load plan {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1107
Agent {0} created session {1} ({2}) in work repository {3}.

Category:
Other

Cause:
null

Action:
null

ODI-1108
Agent {0} created session {1} ({2}) from scenario {3} in work repository {4} using context {5}.

Category:
Other

Cause:
null

Action:
null

ODI-1109
Agent {0} is delegating session {1} on work repository {2} to agent {3}.

Category:
Other

Cause:
null

Action:
null

ODI-1110
Agent {0} successfully retrieved {1} schedules from work repository {2} using {3}.

Category:
Other

Cause:
null

Action:
null

ODI-1111
Agent {0} started. Agent version: {1}. Port: {2}. JMX Port: {3}.

Category:
Other

Cause:
null

Action:
null

ODI-1112
Agent {0} received a request to recalculate its schedule on work repository {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1113
Agent {0} received a data server test request for {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1114
Agent {0} received a request to stop load plan instance {1} on work repository {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1115
Agent {0} received a ping request.

Category:
Other

Cause:
null

Action:
null

ODI-1116
Agent {0} received a request to retrieve its schedule on work repository {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1117
Agent {0} received a request to restart load plan instance ({1}) in work repository {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1118
Agent {0} received a request to start load plan {1} on work repository {2} using context {3}.

Category:
Other

Cause:
null

Action:
null

ODI-1119
Agent {0} received a request to start scenario {1}.{2} on work repository {3} using context {4}.

Category:
Other

Cause:
null

Action:
null

ODI-1120
Agent {0} received a request to restart session {1} on work repository {2} using context {3}.

Category:
Other

Cause:
null

Action:
null

ODI-1121
Agent {0} received a request to stop session {1} on work repository {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1122
Agent {0} successfully restarted {1} queued sessions from work repository {2} using {3}.

Category:
Other

Cause:
null

Action:
null

ODI-1123
Agent {0} sent a request to agent {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1124
Agent {0} started load plan {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1125
Agent {0} started session {1} ({2}) from scenario {3} in work repository {4} using context {5}.

Category:
Other

Cause:
null

Action:
null

ODI-1126
Agent {0} started session {1} ({2}) in work repository {3} using context {4}.

Category:
Other

Cause:
null

Action:
null

ODI-1127
Agent {0} started step {1} in session {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1128
Agent {0} is starting. Container: {1}. Agent Version: {2}. Port: {3}. JMX Port: {4}.

Category:
Other

Cause:
null

Action:
null

ODI-1129
Agent {0} stopped.

Category:
Other

Cause:
null

Action:
null

ODI-1130
Agent {0} is stopping.

Category:
Other

Cause:
null

Action:
null

ODI-1131
Agent {0} encountered an error: {1}

Category:
Other

Cause:
null

Action:
null

ODI-1132
Agent {0} encountered a warning: {1}

Category:
Other

Cause:
null

Action:
null

ODI-1133
Agent {0} detected that the work repository {1} went down.

Category:
Other

Cause:
null

Action:
null

ODI-1134
Agent {0} encountered an error: {1}

Category:
Other

Cause:
null

Action:
null

ODI-1135
Agent {0} detected that the master repository went down.

Category:
Other

Cause:
null

Action:
null

ODI-1136
Starting Schedulers on Agent {0}.

Category:
Other

Cause:
null

Action:
null

ODI-1137
Scheduler started for work repository {0} on Agent {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1138
Migrating Schedulers for Agent {0}.

Category:
Other

Cause:
null

Action:
null

ODI-1139
The current task of the session ({0}) does not support stop immediate. This session will be stopped normally by the Agent ({1}) before next task begins.

Category:
Other

Cause:
null

Action:
null

ODI-1140
Unable to stop session ({0}) immediately. This session will be stopped by the agent ({1}) before next task begins.

Category:
Other

Cause:
null

Action:
null

ODI-1141
Agent {0} started load plan instance {1} ({2}), run {3} in work repository {4}.

Category:
Other

Cause:
null

Action:
null

ODI-1142
Agent {0} successfully completed load plan instance {1} ({2}), run {3} in work repository {4}.

Category:
Other

Cause:
null

Action:
null

ODI-1143
Agent {0} started computing next steps from step {5} of load plan instance {1} ({2}), run {3} in work repository {4}. Triggering session={6}.

Category:
Other

Cause:
null

Action:
null

ODI-1144
Agent {0} completed computing next steps from step {5} of load plan instance {1} ({2}), run {3} in work repository {4}. Triggering session={6}.

Category:
Other

Cause:
null

Action:
null

ODI-1145
Agent {0} not found when trying to stop session with id {1} in work repository {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1146
Agent {0} invocation error when trying to stop session with id {1} in work repository {2}: {3}

Category:
Other

Cause:
null

Action:
null

ODI-1147
Agent {0} stopped load plan instance {1} ({2}), run {3} in work repository {4}.

Category:
Other

Cause:
null

Action:
null

ODI-1148
Agent {0} executing load plan log purge for work repository {1} at {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1151
Agent {0} cannot continue load plan instance {1} ({2}), run {3} in work repository {4}, because the instance has been deleted.

Category:
Other

Cause:
null

Action:
null

ODI-1152
Agent {0} continuing processing for load plan instance {1} ({2}), run {3} in work repository {4}.

Category:
Other

Cause:
null

Action:
null

ODI-1153
An exception occurred while processing scheduled job for scenario {0} and version {1}. The exception message is : {2}

Category:
Other

Cause:
null

Action:
null

ODI-1154
An exception occurred while processing scheduled job for loadplan {0}. The exception message is : {1}

Category:
Other

Cause:
null

Action:
null

ODI-1155
Invalid repetition interval {0} specified in scheduled job for scenario {1} {2}. The schedule would not be repeated.

Category:
Other

Cause:
null

Action:
null

ODI-1156
Invalid repetition interval {0} specified in scheduled job for loadplan {1}. The schedule would not be repeated.

Category:
Other

Cause:
null

Action:
null

ODI-1157
Coherence cluster property {0} is not found in the system properties for Agent {1}. Agent may connect to an unintended coherence cluster.

Category:
Other

Cause:
null

Action:
null

ODI-1158
Agent {0} started invoking load plan exception handler {5} for failed step {6} of load plan instance {1} ({2}), run {3} in work repository {4}. Caused by: step {6}: {7}

Category:
Other

Cause:
null

Action:
null

ODI-1159
Agent {0} completed load plan exception handler {5} for failed step {6} of load plan instance {1} ({2}), run {3} in work repository {4}.

Category:
Other

Cause:
null

Action:
null

ODI-1160
Agent {0} started processing load plan step {5} of load plan instance {1} ({2}), run {3} in work repository {4}.

Category:
Other

Cause:
null

Action:
null

ODI-1161
Agent {0} completed load plan step {5} (status={6}) of load plan instance {1} ({2}), run {3} in work repository {4}.

Category:
Other

Cause:
null

Action:
null

ODI-1162
Scheduled task failed with id {0} of work repository {1} on Agent {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1163
The load plan logs purge operation failed on Agent {0}: {1}

Category:
Other

Cause:
null

Action:
null

ODI-1165
Client requires a repository with version {0} but the repository version found is {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1166
Connection to Enterprise Scheduler {0} succeeded with url={1}, factory={2}, JNDI Name={3}, user={4}

Category:
Other

Cause:
null

Action:
null

ODI-1167
Connection to Enterprise Scheduler {0} failed with url={1}, factory={2}, JNDI Name={3}, user={4}

Category:
Other

Cause:
null

Action:
null

ODI-1168
Authentication failed while connection to REST URL : {0}

Category:
Other

Cause:
null

Action:
null

ODI-1169
Resource not found response for REST URL : {0}. URL not mapped to a REST resource

Category:
Other

Cause:
null

Action:
null

ODI-1170
Bad Request error for REST URL : {0}. Insufficient parameter(s) in the request

Category:
Other

Cause:
null

Action:
null

ODI-1171
Invalid REST base path URL : {0}

Category:
Other

Cause:
null

Action:
null

ODI-1172
Valid REST base path URL : {0}

Category:
Other

Cause:
null

Action:
null

ODI-1173
Method not allowed error for OPTIONS call on the URL : {0}. It can be a valid REST path

Category:
Other

Cause:
null

Action:
null

ODI-1174
Unable to determine the validity of URL : {0}

Category:
Other

Cause:
null

Action:
null

ODI-1175
Allowed Methods : {0}

Category:
Other

Cause:
null

Action:
null

ODI-1176
HTTP Method Used: {0}

Category:
Other

Cause:
null

Action:
null

ODI-1177
Tool Invocation Time : {0}

Category:
Other

Cause:
null

Action:
null

ODI-1178
Request URI : {0} Request Headers : {1}

Category:
Other

Cause:
null

Action:
null

ODI-1179
Response Code : {0} Response Message : {1} Response Family : {2} Response Headers : {3} Response Metadata : {4} Response MediaType : {5} Response Error Message : {6}

Category:
Other

Cause:
null

Action:
null

ODI-1180
Response: not available

Category:
Other

Cause:
null

Action:
null

ODI-1181
System property {0} is not defined

Category:
Other

Cause:
null

Action:
null

ODI-1182
Unable to resolve key {0} to a file. details follow :

Category:
Other

Cause:
null

Action:
null

ODI-1183
Lookup of class for {0} failed

Category:
Other

Cause:
null

Action:
null

ODI-1184
Lookup of key {1} returned class {1}, but class was not found in classpath

Category:
Other

Cause:
null

Action:
null

ODI-1185
Lookup of JAR for {0} failed

Category:
Other

Cause:
null

Action:
null

ODI-1186
Lookup of {0} returned JAR {1}, but JAR was not found

Category:
Other

Cause:
null

Action:
null

ODI-1187
The argument {0}, used as the path ({1}), was not found

Category:
Other

Cause:
null

Action:
null

ODI-1188
One of the System properties {0} or {1} must be defined

Category:
Other

Cause:
null

Action:
null

ODI-1189
Authentication failed while connection to BDC REST URL : {0}

Category:
Other

Cause:
null

Action:
null

ODI-1190
Resource not found response for BDC REST URL : {0}. URL not mapped to a REST resource

Category:
Other

Cause:
null

Action:
null

ODI-1191
Bad Request error for BDC REST URL : {0}. Insufficient parameter(s) in the request

Category:
Other

Cause:
null

Action:
null

ODI-1192
Invalid BDC REST base path URL : {0}

Category:
Other

Cause:
null

Action:
null

ODI-1193
Valid BDC REST base path URL : {0}

Category:
Other

Cause:
null

Action:
null

ODI-1194
Method not allowed error for OPTIONS call on the BDC REST URL : {0}. It can be a valid REST path

Category:
Other

Cause:
null

Action:
null

ODI-1195
Unable to determine the validity of BDC REST URL : {0}

Category:
Other

Cause:
null

Action:
null

ODI-1196
Allowed Methods : {0}

Category:
Other

Cause:
null

Action:
null

ODI-1200
Session start failure: the request is incorrectly formed.

Category:
Other

Cause:
A malformed request was sent to the agent.

Action:
Verify the request format and parameters sent to the agent.

ODI-1201
Session start failure on agent {0}: JDBC connection error occurs while connecting to the master repository.

Category:
Other

Cause:
An incorrect connection was used for the master repository database, or repository database was down.

Action:
Verify the master repository connection information and the status of the master repository database.

ODI-1202
Session start failure on agent {0}: data source for master repository does not contain a master repository.

Category:
Other

Cause:
The master repository connection information pointed to a database schema that did not contain a master repository.

Action:
Verify the master repository connection information.

ODI-1203
Session start failure on agent {0}: the master repository is in an invalid state.

Category:
Other

Cause:
The master repository was in a state that did not allow connections. This is the case if an upgrade was being performed.

Action:
Verify the state of the master repository.

ODI-1204
Session start failure on agent {0}: the master repository version {1} is not compatible with the agent version {2}.

Category:
Other

Cause:
The master repository was upgraded but not this agent, or the agent was upgraded but not the master repository.

Action:
Upgrade the master repository version or the agent version.

ODI-1205
Session start failure on agent {0}: an authentication error occurred while connecting to the master repository.

Category:
Other

Cause:
An incorrect ODI user or password was specified for this master repository.

Action:
Verify the ODI user and password used for connecting.

ODI-1206
Session start failure on agent {0}: the agent is not defined in the topology for master repository.

Category:
Other

Cause:
The session was not found in the master repository.

Action:
Verify that a session with this ID exists in the repository.

ODI-1207
Session start failure on agent {0}: JDBC connection error occurs while connecting to the work repository {1}.

Category:
Other

Cause:
An incorrect connection was used for the work repository database, or repository database was down.

Action:
Verify the work repository connection information and the status of the work repository database.

ODI-1208
Session start failure on agent {0}: database schema {1} does not contain a work repository.

Category:
Other

Cause:
The work repository connection information pointed to a database schema that did not contain a work repository.

Action:
Verify the work repository connection information.

ODI-1209
Session start failure on agent {0}: work repository {1} is in an invalid state.

Category:
Other

Cause:
The work repository was in a state that did not allow connections. This is the case if an upgrade was being performed.

Action:
Verify the state of the work repository.

ODI-1210
Session start failure on agent {0}: work repository {1} version {2} is not compatible with the agent version {3}.

Category:
Other

Cause:
The work repository was upgraded but not this agent, or the agent was upgraded but not the work repository.

Action:
Upgrade the work repository version or the agent version.

ODI-1211
Session start failure on agent {0}: work repository {1} is not bound to the master repository.

Category:
Other

Cause:
The work repository specified in the request was not found in the list of work repositories attached to this master.

Action:
Verify that work repository name matches an existing one.

ODI-1212
Session preparation failure: scenario {0} does not exist in work repository {1}.

Category:
Other

Cause:
The session request was received, but the agent was unable to find the named scenario in the work repository.

Action:
Verify that the scenario name matches an existing scenario name in the work repository.

ODI-1213
Session preparation failure: scenario {0} version {1} does not exist in work repository {2}.

Category:
Other

Cause:
The session request was received, and the scenario existed in the work repository, but not with the specified version.

Action:
Ensure that the scenario version matches an existing scenario version in the work repository.

ODI-1214
Session preparation failure: context {0} does not exist in the master repository.

Category:
Other

Cause:
The session request was received, but the agent was unable to find the context in the master repository.

Action:
Ensure that the context matches an existing context code in the Topology.

ODI-1215
Session preparation failure: privileges are insufficient to run scenario {0}.{1} in repository {2}.

Category:
Other

Cause:
User privileges were not sufficient for running this scenario in this repository.

Action:
Ensure that the user has sufficient privileges for this task.

ODI-1216
Session preparation failure: insufficient privileges to use Context {0} ({1}).

Category:
Other

Cause:
User privileges were not sufficient for using this context.

Action:
Ensure that the user has sufficient privileges for this task.

ODI-1217
Session {0} ({1}) fails with return code {2}.

Category:
Other

Cause:
The session finished in an error state.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1218
Session preparation failure: database error occurs while connecting to the master repository.

Category:
Other

Cause:
The agent received a database error from the master repository while creating the session.

Action:
Verify the state of the master repository database.

ODI-1219
Session preparation failure: database error while connecting to work repository {0}.

Category:
Other

Cause:
The agent received a database error from the work repository while creating the session.

Action:
Verify the state of the work repository database.

ODI-1220
Session preparation failure: an unexpected exception occurred.

Category:
Other

Cause:
The remote agent faced an unexpected error while attempting to create the session.

Action:
Contact Oracle Support Services. Provide the error message, a description of the action causing this fault, and the exception stack trace in the log files (with the logging level set to debug mode).

ODI-1221
Unable to restart session {0}: session is not found in work repository {1}.

Category:
Other

Cause:
The session to restart did not exist in the repository. This session may have been deleted, or an incorrect session ID or work repository was supplied.

Action:
Verify that a session with this ID exists in the repository.

ODI-1222
Session start failure on agent {0}: logical schema {1} cannot be found in the master repository.

Category:
Other

Cause:
The object to be executed referred to a logical schema not present in the master repository.

Action:
Ensure that the logical schema configuration exists in your master repository.

ODI-1223
Database error while connecting to the master repository.

Category:
Other

Cause:
The connection for the master repository database was incorrect, or the repository database was down.

Action:
Verify the master repository connection information and the status of the master repository database.

ODI-1224
Database error while connecting to work repository {0}

Category:
Other

Cause:
The connection for the work repository database was incorrect, or the repository database was down.

Action:
Verify the work repository connection information and the status of the master repository database.

ODI-1225
An unexpected exception occurred.

Category:
Other

Cause:
The agent faced an unexpected exception.

Action:
Contact Oracle Support Services. Provide the error message, a description of the action causing this fault, and the exception stack trace in the log files (with the logging level set to debug mode).

ODI-1226
Step {0} fails after {1} attempt(s).

Category:
Other

Cause:
This is an execution warning. The session step failed to execute after the maximum number of retries. If step failure was not handled in the package design, the session finished in an error state.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1227
Task {0} fails on the source connection {1}.

Category:
Other

Cause:
This is an execution warning. The command on the source for this task finished with an error.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1228
Task {0} fails on the target connection {1}.

Category:
Other

Cause:
This is an execution warning. The command on the target for this task finished with an error.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1229
An error occurred while performing a {0} operation on model code {1}.

Category:
Other

Cause:
This is an execution warning. The operation specified failed on the model.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1231
An error occurred while performing a {0} operation on datastore {1}.

Category:
Other

Cause:
This is an execution warning. The operation specified failed on the datastore.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1232
Procedure {0} execution fails.

Category:
Other

Cause:
This is an execution warning. The procedure execution failed.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1233
Error while evaluating variable the following expression: {0} {1} {2}

Category:
Other

Cause:
This is an execution warning. The variable evaluation failed.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1235
Error while incrementing variable {0} to value {1}

Category:
Other

Cause:
This is an execution warning. The variable increment failed.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1236
Error while refreshing variable {0}.

Category:
Other

Cause:
This is an execution warning. The variable refresh failed.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1237
Error while setting variable {0} to value {1}.

Category:
Other

Cause:
This is an execution warning. The set variable operation failed.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1238
Flow {0} fails because the maximum number of allowed errors ({1} rows) is exceeded during the flow check. This flow loads target table {2}.

Category:
Other

Cause:
This is an execution warning. The interface failed because the number of errors detected in the flow exceeded the value defined in the interface.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer. Review the erroneous records for this interface in the error table.

ODI-1239
Flow {0} fails because the maximum percentage of allowed errors ({1} %) is exceeded during the flow check. This flow loads target table {2}.

Category:
Other

Cause:
This is an execution warning. The interface failed because the percentage of errors detected in the flow exceeded the value defined in the interface.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer. Review the erroneous records for this interface in the error table.

ODI-1240
Flow {0} fails while performing a {1} operation. This flow loads target table {2}.

Category:
Other

Cause:
This is an execution warning. The interface failed because one of the statements returned an error return code.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1241
Oracle Data Integrator tool execution fails.

Category:
Other

Cause:
This is an execution warning. The tool execution failed.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1242
Operating system command execution fails.

Category:
Other

Cause:
This is an execution warning. Execution of the operating system command failed.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1243
Session {0} ({1}) fails because work repository {2} went down.

Category:
Other

Cause:
Work repository database went down while session was being executed.

Action:
Verify the state of the work repository database. The session must be restarted.

ODI-1244
Session {0} {1} was prepared successfully but fails because work repository {2} went down before execution could begin.

Category:
Other

Cause:
Work repository database went down while session was starting its execution.

Action:
Verify the state of the work repository database. The session must be restarted.

ODI-1245
Session preparation failure: work repository {0} went down during session preparation.

Category:
Other

Cause:
Work repository went down while session was being prepared.

Action:
Verify the state of the work repository database. The session must be restarted.

ODI-1246
The Logical Schema has not been set for {0}.

Category:
Other

Cause:
Because the logical schema had not been set, the object could not be executed.

Action:
Verify the object that you are trying to execute, and set the logical schema for this object.

ODI-1247
Session {0} {1} was prepared successfully but fails because master repository went down before execution could begin.

Category:
Other

Cause:
Master repository database went down while session was starting its execution.

Action:
Verify the state of the master repository database. The session must be restarted.

ODI-1248
Session preparation failure by Agent {0}: master repository went down during session preparation.

Category:
Other

Cause:
Master repository went down while session was being prepared.

Action:
Verify the state of the master repository database. The session must be restarted.

ODI-1249
Session {0} ({1}) fails because master repository went down.

Category:
Other

Cause:
Master repository database went down while session was being executed.

Action:
Verify the state of the master repository database. The session must be restarted.

ODI-1250
Session {0} ({1}) could not be stopped by Agent {2} because session {0} {1} already completed execution.

Category:
Other

Cause:
The session has already completed and cannot be stopped.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1251
Session ({0}) could not be stopped by Agent {1} because session ({0}) was not found in work repository {2}.

Category:
Other

Cause:
The session was not found in the work repository.

Action:
Verify that a session with this ID exists in the repository.

ODI-1252
Session ({0}) could not be stopped by Agent {1}: insufficient privileges to access session.

Category:
Other

Cause:
User privileges were not sufficient for accessing this session in this agent.

Action:
Ensure that the user has sufficient privileges for this task.

ODI-1253
Session {0} ({1}) could not be stopped by Agent {2}: an unknown error occurred.

Category:
Other

Cause:
An unexpected Exception occurred.

Action:
Verify your Agent configuration and make sure other operations on Agent are working correctly.

ODI-1254
Session {0} ({1}) could not be stopped by Agent {2}: a JDBC error occurred on work repository {3}.

Category:
Other

Cause:
The agent had incorrect connection for the work repository database, or repository database was down.

Action:
Verify the work repository connection information and the status of the work repository database.

ODI-1255
Session {0} ({1}) could not be stopped by Agent {2}: insufficient privileges to stop the session.

Category:
Other

Cause:
User privileges were not sufficient for stopping this session in this agent.

Action:
Ensure that the user has sufficient privileges for this task.

ODI-1256
Session {0} ({1}) stopped (Normal) by user {2}.

Category:
Other

Cause:
Session was stopped by the user.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1257
Session {0} ({1}) stopped (Immediate) by user {2}.

Category:
Other

Cause:
Session was stopped by the user.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1258
Session {0} ({1}) stopped (Abort) by user {2}.

Category:
Other

Cause:
Session was aborted by the user.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1259
Session Task {0} stopped (Normal) by user {1}.

Category:
Other

Cause:
Task was stopped by the user.

Action:
Review the task execution details in the Operator Navigator or Repository Explorer.

ODI-1260
Session Task {0} stopped (Immediate) by user {1}.

Category:
Other

Cause:
Task was stopped by the user.

Action:
Review the task execution details in the Operator Navigator or Repository Explorer.

ODI-1261
Session Task {0} stopped (Abort) by user {1}.

Category:
Other

Cause:
Task was aborted by the user.

Action:
Review the task execution details in the Operator Navigator or Repository Explorer.

ODI-1262
Session {0} ({1}) could not be stopped by Agent {2}: a JDBC error occurred on master repository.

Category:
Other

Cause:
The agent had incorrect connection for the master repository database, or repository database was down.

Action:
Verify the master repository connection information and the status of the master repository database.

ODI-1263
Step {0} stopped (Normal) by user {1}.

Category:
Other

Cause:
Step was stopped by the user.

Action:
Review the step execution details in the Operator Navigator or Repository Explorer.

ODI-1264
Step {0} stopped (Immediate) by user {1}.

Category:
Other

Cause:
Step was stopped by the user.

Action:
Review the step execution details in the Operator Navigator or Repository Explorer.

ODI-1265
Step {0} stopped (Abort) by user {1}.

Category:
Other

Cause:
Step was aborted by the user.

Action:
Review the step execution details in the Operator Navigator or Repository Explorer.

ODI-1266
Agent {0} detected Session as stale session and set to error status.

Category:
Other

Cause:
The agent detected a stale session and the session status was set to error status.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1267
Session ({0}) could not be stopped by Agent {1} because stop type {2} provided in the request is an invalid stop type.

Category:
Other

Cause:
The agent attempted to stop a session with an invalid stop type.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1268
Agent {0} does not support stopping asynchronous child sessions.

Category:
Other

Cause:
The agent attempted to stop an asynchronous child session and this is not supported.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1269
Session {0} ({1}) could not be stopped by Agent {2}: session is being run by another Agent with the same name.

Category:
Other

Cause:
The agent attempted to stop a session that is being run by a different agent.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1270
Session {0} ({1}) could not be stopped by Agent {2}: session {0} ({1}) is being run by {3} Agent which is not a listener Agent.

Category:
Other

Cause:
The agent attempted to stop a session that is being run by the internal agent and this is not supported.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1271
The asynchronous jndi name cannot be null for asynchronous jobs. The ESS job status cannot be updated.

Category:
Other

Cause:
The agent attempted to set the status of the asynchronous ESS job and its jndi name was not set.

Action:
Review the jndi name supplied to the Enterprise Scheduler job.

ODI-1272
The Logical Schema has not been set on {0} for {1}.

Category:
Other

Cause:
The logical schema for this object has not been set.

Action:
Verify that the logical schema has been set in the Topology.

ODI-1273
The selected technology {0} is not supported on source for {1}.

Category:
Other

Cause:
The selected technology is not supported for this object.

Action:
Verify that the object has a valid technology.

ODI-1274
Agent Exception

Category:
Other

Cause:
An error was detected by the agent when performing an operation.

Action:
Review the underlying exception for more details.

ODI-1275
An error occurred while performing a {0} operation on submodel step {1} of the model code {2}.

Category:
Other

Cause:
This is an execution warning. The operation specified failed on the submodel operation.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1276
An error occurred while executing the OnConnect command on JDBC connection created for data server {0} with transaction label {1}.

Category:
Other

Cause:
An error was occurred while executing the OnConnect command on the JDBC connection created to the data server.

Action:
Review the underlying exception and update the OnConnect command definition configured for the data server.

ODI-1277
An error occurred while executing the OnDisconnect command on JDBC connection created for data server {0} with transaction label {1}.

Category:
Other

Cause:
An error was occurred while executing the OnDisconnect command on the JDBC connection created to the data server.

Action:
Review the underlying exception and update the OnDisconnect command definition configured for the data server.

ODI-1278
Load plan instance {0}, run {1} does not exist in work repository {2}.

Category:
Other

Cause:
The Load Plan Instance run does not exist in the repository. This Load Plan Instance run may have been deleted, or an incorrect instance ID/run number or work repository was supplied.

Action:
Verify that a load plan instance run with this instance ID and run number exists in the repository.

ODI-1279
The Source Logical Schema {0} and Context {1} of the task {2} are not mapped to any Physical Schema.

Category:
Other

Cause:
The Logical Schema to Physical Schema Mapping is not defined for the Context used.

Action:
For the Context used define the Logical Schema to Physical Schema Mapping in the Topology.

ODI-1280
The Target Logical Schema {0} and Context {1} of the task {2} are not mapped to any Physical Schema.

Category:
Other

Cause:
The Logical Schema to Physical Schema Mapping is not defined for the Context used.

Action:
For the Context used define the Logical Schema to Physical Schema Mapping in the Topology.

ODI-1281
Source Technology {0} of task {1} is not of JDBC Type. When both Source and Target commands are specified, the Source Technology should be of JDBC type.

Category:
Other

Cause:
When Source and Target commands are specified, the Source Technology should always be of JDBC type.

Action:
Make Sure that you modify your Procedure or KM to either use a JDBC Source Technology or edit your step to use only the Target command.

ODI-1282
Invalid log level {0} is specified. A valid log level value is between {1} and {2}.

Category:
Other

Cause:
Invalid log level specified for scenario/session invocation or for session restart.

Action:
Please specify a valid log level.

ODI-1283
Owb preparation failure: Owb object {0} of type {1} in location {2} does not exist in Owb repository {3}.

Category:
Other

Cause:
The session request was received, but the agent was unable to find the named Owb object in the Owb repository.

Action:
Verify that the Owb object name matches an existing Owb object in the location in the Owb repository.

ODI-1284
Session {0} ({1}) with Owb audit Id {2} fails.

Category:
Other

Cause:
The session finished in an error state.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1285
Session {0} ({1}) Retreival of audit for auditId {2} failed in the {3} phase {4}. Please use OWB Design Client or Browser for further information.

Category:
Other

Cause:
An error was raised during the retreival of the Owb audit data.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer. Also please use OWB Design Client or Browser for further information.

ODI-1286
Session {0} ({1}) could not find Owb job for this session.

Category:
Other

Cause:
The session being aborted is not an Owb Job.

Action:
Review the session being aborted in the Operator Navigator or Repository Explorer.

ODI-1287
Session {0} ({1}) with Owb audit Id {2} is in an invalid state to be aborted.

Category:
Other

Cause:
The session being aborted is not in a state that can be aborted.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer. Also please use OWB Design Client or Browser for further information.

ODI-1288
Session {0} ({1}) with Owb audit Id {2} abort fails.

Category:
Other

Cause:
The session abort finished in an error state.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer. Also please use OWB Design Client or Browser for further information.

ODI-1289
Agent {0} detected Session as stale session and set to error status. Please use OWB Design Client or Browser for further information.

Category:
Other

Cause:
The agent detected a stale OWB session and the session status was set to error status.

Action:
Review the session execution details in the OWB Design Client or Browser.

ODI-1290
Session {0} ({1}) Loading of audit for auditId {2} failed in the {3} phase {4}.

Category:
Other

Cause:
An error was raised during the loading of the Owb audit data.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer. Also please use OWB Design Client or Browser for further information.

ODI-1291
Workspace {0} cannot be resolved to a physical workspace using context {1}.

Category:
Other

Cause:
The context does not contain a mapping for the logical workspace.

Action:
Review the mappings defined in the context.

ODI-1292
An execution context cannot be determined for this job.

Category:
Other

Cause:
An execution context cannot be determined for this job.

Action:
Use the Context to provide an explicit context for this execution.

ODI-1293
Exception occurred during spawning of ECID to child session.

Category:
Other

Cause:
Spawning of ECID from parent session to child session failed.

Action:
Review the exception raised to get more detail.

ODI-1294
Unwrapping of a wrapped ECID [{0}] failed.

Category:
Other

Cause:
Unwrapping of ECID failed.

Action:
Review the exception raised and the format of wrapped ECID to get more detail on unwrap failure

ODI-1295
Cleanup of Session {0} ({1}) raised the following {2} messages: {3}

Category:
Other

Cause:
Messages were raised during the Cleanup phase.

Action:
Review the messages raised during the Cleanup and you may need to perform some manual cleanup.

ODI-1296
The Cleanup Tool encountered the following {0} nested errors when executing the Cleanup tasks: {1}

Category:
Other

Cause:
Messages were raised during the Cleanup tool execution.

Action:
Review the messages raised during the Cleanup and you may need to perform some manual cleanup.

ODI-1297
Parallel task "{0}" failed; {1} child task(s) in error; Failed child tasks: {2}

Category:
Other

Cause:
null

Action:
null

ODI-1298
Serial task "{0}" failed because child task "{1}" is in error.

Category:
Other

Cause:
null

Action:
null

ODI-1299
A task "{0}" from one of the parallel branches has failed. Hence aborting the current branch

Category:
Other

Cause:
null

Action:
null

ODI-1300
ASYNC_JNDI_NAME cannot be null for async job.

Category:
Other

Cause:

Action:

ODI-1301
Unable to submit Job Definition: {0}

Category:
Other

Cause:

Action:

ODI-1302
Logical Agent {0} must be mapped to a Physical Agent in the ContextCode {1}

Category:
Other

Cause:

Action:

ODI-1303
RuntimeSessionfactory must not be null.

Category:
Other

Cause:

Action:

ODI-1304
Unable to find request for ID {0}

Category:
Other

Cause:

Action:

ODI-1305
jobDefinitionId must not be null

Category:
Other

Cause:

Action:

ODI-1306
scheduleDefinitionId must not be null

Category:
Other

Cause:

Action:

ODI-1307
ContextCode is null, cannot lookup physical agent

Category:
Other

Cause:

Action:

ODI-1308
SchedulingService object was created without an EntityManager, cannot lookup physical agent

Category:
Other

Cause:

Action:

ODI-1309
Unable to find logical agent : {0}.

Category:
Other

Cause:

Action:

ODI-1310
Unable to find context : {0}.

Category:
Other

Cause:

Action:

ODI-1311
JobDefinition with name {0} already exists.

Category:
Other

Cause:
JobDefinition already exists.

Action:
Check JobDefinition name.

ODI-1312
Schedule with name {0} already exists.

Category:
Other

Cause:
Schedule already exists.

Action:
Check Schedule name.

ODI-1313
Unable to find job definition for ID {0}.

Category:
Other

Cause:
Wrong ID.

Action:
Check ID.

ODI-1314
Unable to find job definition with name {0}.

Category:
Other

Cause:
Wrong name.

Action:
Check name.

ODI-1315
Unable to update job definition.

Category:
Other

Cause:
Exception during updating.

Action:
Check cause exception details.

ODI-1316
Unable to remove job request.

Category:
Other

Cause:
Exception was thrown.

Action:
Check cause exception details.

ODI-1317
Unable to find scheduler definition with name {0}.

Category:
Other

Cause:
Wrong name.

Action:
Check name.

ODI-1318
jobDefnition is required to have a not null ID.

Category:
Programmatic

Cause:
Metadata Object ID is null.

Action:
Check job definition.

ODI-1319
Error while refreshing variable {0}. Null/Empty refresh query is provided.

Category:
Other

Cause:
This is an execution warning. The variable refresh failed.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-1320
Session start/restart failure on agent {0}: the session {1} is not in status WAITING, ERROR or WARNING

Category:
Other

Cause:
The session cannot be started/restarted because it is not in status WAITING, ERROR or WARNING

Action:
Verify that a session with this ID exists in the repository and status WAITING, ERROR or WARNING.

ODI-1350
Credential map key "{0}" not found in credential map "{1}".

Category:
Other

Cause:

Action:

ODI-1351
An unexpected error was thrown during execution of the scenario "{0} - {1}"

Category:
Other

Cause:

Action:

ODI-1352
An unexpected error was thrown during job execution

Category:
Other

Cause:

Action:

ODI-1353
RequestId={0} Scenario={1} : Agent URL must be specified. The Job Definition must include the LocalAgent or the job submission must include a physical agent url ({2}) parameter.

Category:
Other

Cause:

Action:

ODI-1354
Load plan must be asynchronous

Category:
Other

Cause:

Action:

ODI-1355
username "{0}" from credential map "{1}" does not match currentSubjectName "{2}"

Category:
Other

Cause:

Action:

ODI-1356
Credential map key parameter "{0}" not found.

Category:
Other

Cause:

Action:

ODI-1357
Error resolving ADF connection for connectionId="{0}".

Category:
Other

Cause:

Action:

ODI-1400
Agent {0} start failure: JDBC connection error occurs while connecting to the master repository.

Category:
Other

Cause:
The master repository information was incorrect, or the repository database was down.

Action:
Verify the master repository connection information and the status of the master repository database.

ODI-1401
Agent {0} start failure: data source for master repository did not contain a master repository.

Category:
Other

Cause:
The master repository connection information pointed to a database schema that did not contain a master repository.

Action:
Verify the master repository connection information.

ODI-1402
Agent {0} start failure: the master repository is in an invalid state.

Category:
Other

Cause:
The master repository was in a state that did not allow connections. This is the case when an upgrade is being performed.

Action:
Verify the state of the master repository.

ODI-1403
Agent {0} start failure: the master repository version {1} is not compatible with the agent version {2}.

Category:
Other

Cause:
The master repository was upgraded but not this agent, or the agent was upgraded but not the master repository.

Action:
Upgrade the master repository version or the agent version.

ODI-1404
Agent {0} start failure: an authentication error occurred while connecting to the master repository.

Category:
Other

Cause:
An incorrect ODI user or password was specified for this master repository.

Action:
Verify the ODI user and password used for connecting.

ODI-1405
Agent {0} start failure: the agent is not defined in the topology for master repository.

Category:
Other

Cause:
This agent was not declared in the topology.

Action:
Add this physical agent in the list of agents in the ODI topology.

ODI-1406
Agent {0} started with warning: JDBC connection error occurs while connecting to the work repository {1}.

Category:
Other

Cause:
The work repository information was incorrect, or the repository database was down.

Action:
Verify the work repository connection information and the status of the work repository database.

ODI-1407
Agent {0} started with warning: connection details of {1} do not contain a work repository.

Category:
Other

Cause:
The work repository connection information pointed to a database schema that did not contain a work repository.

Action:
Review the work repository connection information and revise it as necessary.

ODI-1408
Agent {0} started with warning: work repository {1} is in an invalid state.

Category:
Other

Cause:
The work repository was in a state that did not allow connections. This is the case when an upgrade is being performed.

Action:
Verify the state of the work repository.

ODI-1409
Agent {0} started with warning: work repository {1} version {2} is not compatible with the agent version {3}.

Category:
Other

Cause:
The work repository was upgraded but not this agent, or the agent was upgraded but not the work repository.

Action:
Upgrade the work repository version or the agent version.

ODI-1410
Agent {0} started with warning: work repository {1} is not bound to the master repository.

Category:
Other

Cause:
The work repository specified in the request was not found in the list of work repositories attached to this master.

Action:
Ensure that work repository name matches an existing one.

ODI-1411
Agent {0} started with warning: a database error occurs while cleansing stale sessions.

Category:
Other

Cause:
The agent encountered a database error while attempting to close stale sessions.

Action:
Review the status of the sessions for this agent, and manually remove the stale sessions.

ODI-1412
Agent {0} started with warning: an unexpected error occurs while cleaning stale sessions.

Category:
Other

Cause:
The agent encountered an unexpected error while attempting to close stale sessions.

Action:
Contact Oracle Support Services. Provide the error message, a description of the action causing this fault, and the exception stack trace in the log files (with the logging level set to debug mode). Verify the status of the sessions for this agent, and manually remove the stale sessions.

ODI-1413
Request is incorrectly formed.

Category:
Other

Cause:
A malformed request was sent to the agent.

Action:
Review the request format and parameters sent to the agent.

ODI-1414
Error connecting to agent {0}: a JDBC error occurs while connecting to the master repository.

Category:
Other

Cause:
The remote agent had incorrect connection for the master repository database, or repository database was down.

Action:
Verify the master repository connection information and the status of the master repository database.

ODI-1415
Error connecting to agent {0}: data source for master repository did not contain a master repository.

Category:
Other

Cause:
The master repository connection information for the remote agent pointed to a database schema that did not contain a master repository.

Action:
Review the master repository connection information and revise it as necessary.

ODI-1416
Error connecting to agent {0}: the master repository is in an invalid state.

Category:
Other

Cause:
The master repository was in a state that did not allow connections from the remote agent. This is the case when an upgrade is being performed.

Action:
Verify the state of the master repository.

ODI-1417
Error connecting to agent {0}: the master repository version {1} is not compatible with the agent version {2}.

Category:
Other

Cause:
The master repository was upgraded but not the remote agent, or the remote agent was upgraded but not the master repository.

Action:
Upgrade the master repository version or the agent version.

ODI-1418
Error connecting to agent {0}: an authentication error occurs while connecting to the master repository.

Category:
Other

Cause:
An incorrect ODI user or password was specified for this master repository.

Action:
Verify the ODI user and password used for connecting.

ODI-1419
Warning connecting to Agent {0}: JDBC connection error occurs while connecting to the work repository {1}.

Category:
Other

Cause:
The remote agent had incorrect connection for the work repository database, or the repository database was down.

Action:
Verify the work repository connection information and the status of the work repository database.

ODI-1420
Warning connecting to Agent {0}: connection details of {1} do not contain a work repository.

Category:
Other

Cause:
The work repository connection information for the remote agent pointed to a database schema that did not contain a work repository.

Action:
Verify the work repository connection information.

ODI-1421
Warning connecting to Agent {0}: work repository {1} is in an invalid state.

Category:
Other

Cause:
The work repository was in a state that did not allow connections from the remote agent. This is the case when an upgrade is being performed.

Action:
Verify the state of the work repository.

ODI-1422
Warning connecting to Agent {0}: work repository {1} version {2} is not compatible with the agent version {3}.

Category:
Other

Cause:
The work repository was upgraded but not the remote agent, or the remote agent was upgraded but not the work repository.

Action:
Upgrade the work repository version or the agent version.

ODI-1423
Warning connecting to Agent {0}: work repository {1} is not bound to the master repository.

Category:
Other

Cause:
The work repository specified in the request was not found in the list of work repositories attached to the master.

Action:
Verify that work repository name matches an existing one.

ODI-1424
Agent host or port cannot be reached using {0}.

Category:
Other

Cause:
Incorrect host or port information was provided, or the agent was not started on the remote host.

Action:
Correct the host or port information or start the agent.

ODI-1425
Agent application cannot be reached using {0}.

Category:
Other

Cause:
An incorrect application name was provided for this agent, or the agent application was not started on the host.

Action:
Correct the application name used in the URL or verify the agent status.

ODI-1426
Agent {0} is not defined in the topology for the master repository.

Category:
Other

Cause:
This agent was not declared in the topology.

Action:
Add this physical agent to the list of agents in the ODI topology.

ODI-1427
invalid parameters

Category:
Other

Cause:
Invalid parameters were supplied in the request.

Action:
Check the parameters that were supplied as part of the request. Ensure that parameter names and cases are correct.

ODI-1428
internal error

Category:
Other

Cause:
An agent internal error occurred.

Action:
Contact Oracle Support Services. Provide the error message, a description of the action causing this fault, and the exception stack trace in the log files (with the logging level set to debug mode).

ODI-1429
The user {0} is not authorized to perform request {1} on Agent {2}.

Category:
Other

Cause:
The user had insufficient privileges for performing this request against the remote agent.

Action:
Amend the user privileges.

ODI-1430
Agent {0} cannot clean the stale sessions in work repository {1} due to a database error.

Category:
Other

Cause:
The remote agent faced a database error while attempting to close stale sessions.

Action:
Examine the status of the sessions for this agent, and manually remove the stale sessions.

ODI-1431
Agent {0} cannot clean the stale sessions in work repository {1} because the work repository {1} is still down.

Category:
Other

Cause:
The remote agent was not able to connect to the work repository while attempting to close stale sessions.

Action:
Determine the status of the repository. Once this repository is running, manually remove the stale sessions.

ODI-1432
Agent {0} cannot clean the stale sessions in work repository {1} due to an unexpected error.

Category:
Other

Cause:
The remote agent faced an unexpected error while attempting to close stale sessions.

Action:
Contact Oracle Support Services. Provide the error message, a description of the action causing this fault, and the exception stack trace in the log files (with the logging level set to debug mode). Determine the status of the sessions for this agent, and manually remove the stale sessions.

ODI-1433
The Internal agent does not support cleaning stale sessions from multiple work repositories.

Category:
Other

Cause:
Empty string value was passed for the work repository name in the Clean Stale Sessions request sent to the Internal Agent.

Action:
Specify a non-empty valid work repository name in the Clean Stale Sessions request sent to the Internal Agent. If you want to clean the stale sessions across the work repositories, perform this operation on a Remote physical Agent.

ODI-1434
Agent {0} start failure: error while trying to use JMX Port {1}.

Category:
Other

Cause:
JMX Registry was unable to use the given port.

Action:
Specify a different port by using the command-line parameter JMXPORT.

ODI-1435
Storage space for the IDs of some object types is low in Repository {0}. When no storage space is available, it will not be possible to create obects of these types. Consider creating a new repository for the following object types (Object Type: Number Remaining) {1}.

Category:
Other

Cause:
Storage space was low for some IDs in this repository.

Action:
Consider creating a new repository.

ODI-1436
Error retrieving ID statistics for repository {0}.

Category:
Other

Cause:
The ID statistics for this repository could not be verified.

Action:
Verify the statistics for this repository manually.

ODI-1437
Error retrieving information from the credential store map.

Category:
Other

Cause:
Could not retrieve information from the credential store map.

Action:
Verify that the credentials have been entered correctly into the credential store map.

ODI-1438
Agent {0} cannot be stopped by user {1}: a JDBC error occurred on master repository {2}.

Category:
Other

Cause:
Some SQL Exception occurred on the Master Repository.

Action:
Verify that other operations on the Agent are working correctly.

ODI-1439
Agent {0} cannot be stopped by user {1}: a JDBC error occurred on work repository {2}.

Category:
Other

Cause:
Some SQL Exception occurred on the Work Repository.

Action:
Verify that other operations on the Agent are working correctly.

ODI-1440
Agent {0} cannot be stopped by user {1}: an unknown error occurred.

Category:
Other

Cause:
An unexpected Exception occurred.

Action:
Verify your Agent configuration and make sure other operations on Agent are working correctly.

ODI-1441
Unable to connect to the master repository at JBDC URL={0} with USER={1}.

Category:
Other

Cause:
An SQLException occurred while creating connection to the master repository with the given parameters.

Action:
Verify your Agent configuration and make sure the master repository connection parameters are correct.

ODI-1442
Unable to load JBDC Driver {0} configured for master repository connection.

Category:
Other

Cause:
ClassNotFoundException occurred while loading the driver class.

Action:
Verify your Agent configuration and make sure the driver specified for master repository connection is correct and the corresponding jar is present under driver folder.

ODI-1443
Error while starting agent : {0}

Category:
Other

Cause:
Error occurred while starting the embedded web container.

Action:
Verify your Agent configuration and make sure that the specified ports are available.

ODI-1444
The master repository signature specified by the client {0} does not match the master repository signature of the agent {1}.

Category:
Other

Cause:
The client and the agent are not using the same master repository

Action:
Verify the client and the agent are using the same master repository. Verify that the client is calling the correct agent.

ODI-1445
Invalid HTTP/S URL retrieved from the JRF utility : {0}

Category:
Other

Cause:
JRF utility has returned an invalid HTTP/S URL for the agent.

Action:
Verify if ODI agent's dependent modules are successfully deployed on the container.

ODI-1446
Agent {0} is already running on port {1}.

Category:
Other

Cause:
This agent is already running.

Action:
Stop the agent before attempting to start it.

ODI-1447
Agent {0} failed to start. {1}.

Category:
Other

Cause:
The agent failed to start.

Action:
See the nodemanager and agent log for further information.

ODI-1448
Failed to execute command {1} for agent {0}.

Category:
Other

Cause:
A command failed to execute on the agent.

Action:
Review the agent log for further information.

ODI-1449
Injection risk detected for command {0}. Command not executed.

Category:
Other

Cause:
The command was not executed because it contained characters that pose an injection risk.

Action:
Adjust the command to eliminate characters that pose an injection risk.

ODI-1450
ODI does not support soft restart.

Category:
Other

Cause:
The process management softRestart method was invoked, but it is not supported.

Action:
Do not invoke the softRestart method.

ODI-1451
Using localhost for hostname because of {0} when trying to get hostname.

Category:
Other

Cause:
An exception was thrown while trying to get the actual host name for the local host.

Action:
No action is required as the exception is caught and the host name is defaulted to localhost.

ODI-1452
Agent {0} cannot be started, {1} is already in use by another agent.

Category:
Other

Cause:
An attempt was made to restart the agent, but it is currently in use.

Action:
Wait for other dependent agents to complete before restarting this agent.

ODI-1453
Agent {0} cannot be started, {1} is already in use by another process.

Category:
Other

Cause:
An attempt was made to restart the agent, but it is currently in use.

Action:
Wait for dependent processes to complete before restarting this agent.

ODI-1454
Agent {0} cannot be started at {1}. Unexpected http response = {2}.

Category:
Other

Cause:
The agent cannot be started. It is possible that another processes is already running on the agent port.

Action:
Review the http response to determine the process running on the agent port.

ODI-1455
System componenent creation failed: instanceName={0}, cause={1}

Category:
Other

Cause:
An exception prevented the ODI component from being created.

Action:
Review the exception to determine the cause.

ODI-1456
getServerConfiguration() failed. domainDir={0}, dirPath={1}, instanceName={2}, cause={3}

Category:
Other

Cause:
An exception was thrown while setting the ODI configuration parameters.

Action:
Review the exception text at the end of the message to determine the cause.

ODI-1457
getDBConfiguration() failed. domainDir={0}, dirPath={1}, datasourceName={2}, cause={3}

Category:
Other

Cause:
An exception was thrown while setting the ODI database configuration parameters.

Action:
Review the exception text at the end of the message to determine the cause.

ODI-1458
ODI configuration files found, but a corresponding instance is not configured. dirPath={0}. Cause={1}

Category:
Other

Cause:
An exception was thrown while retrieving database configuration parameters from a file.

Action:
Review the exception text at the end of the message to determine the file name and exception cause.

ODI-1459
Failed to retrieve master repository name and timestamp for agent {0}. Using the values from instance.properties. Cause={1}

Category:
Other

Cause:
An exception was thrown while attempting to read metadata for the master repository.

Action:
Review the exception text at the end of the message to determine the cause.

ODI-1460
Unable to insert into table {0} for concurrent execution control. Exceptions due to competing insertions can happen and are handled to continue execution. Other exceptions likely indicate a runtime problem. Error message: {1}

Category:
Other

Cause:
An exception was raised when inserting a record into the concurrent execution control table.

Action:
Exceptions due to competing insertions can happen and are handled to continue execution. Other exceptions likely indicate a runtime problem.

ODI-1461
{0} job status has changed unexpectedly from {1} to {2} while waiting for its turn to run under concurrent execution control.

Category:
Other

Cause:
The status of a job was likely changed outside of the control of the runtime agent while the job was waiting for its turn to run under concurrent execution control by the agent.

Action:
The job may have been changed outside of the agent, and the agent skipped the job execution. Start the job again if it was not executed.

ODI-1462
{0} job [{1}] should be the last one in the following waiting {0} list: {2}

Category:
Other

Cause:
The job may have been changed or deleted outside of the runtime agent while the job was waiting for its turn to run under concurrent execution control by the agent.

Action:
The job may have been changed or deleted outside of the agent, and the agent skipped the job execution. Start the job again if it was not executed.

ODI-1463
{0} job [{1}] blocked by the following {0} job(s) due to potential concurrent execution condition: {2}{3}

Category:
Other

Cause:
The job was under concurrent execution control with Raise Error violation behavior, and there were existing runnable and/or waiting jobs submitted ahead of the job.

Action:
Start the job when other concurrently running and waiting jobs are completed, or change the job's violation behavior to Wait To Execute before starting the job.

ODI-1464
There is no Hadoop Dataserver selected for PigDataServer- {0} from topology.

Category:
Other

Cause:
Repository Error.

Action:
Verify the dataservers in topology and associate a Hadoop dataserver to Pig dataserver when in Mapreduce mode .

ODI-1465
Error while trying to read values of DataServer- {0} from topology.

Category:
Other

Cause:
Repository Error.

Action:
Verify the dataservers in topology and if needed, associate a Hadoop dataserver to Pig dataserver when in Mapreduce mode.

ODI-1466
Error occurred previewing file on agent {0}

Category:
Other

Cause:
Error previewing file on the agent

Action:
Verify that file configuration is valid. Verify that file is available

ODI-1467
Error occurred trying to find URL of ODI scripting JAR {0}

Category:
Other

Cause:
Error getting the URL of ODI scripting language JAR

Action:
Verify that the path is valid

ODI-1500
SQL Exception when accessing work repository {0} while executing load plan instance {1} - {2}

Category:
Other

Cause:
A SQLException was thrown when trying to update the work repository

Action:
The same set of updates will be attempted later, potentially from a different agent

ODI-1501
Cannot find variable "{0}" in the definition of load plan instance {1}.

Category:
Other

Cause:
The start/restart load plan request contained startup values for variables that are not defined in the load plan

Action:
User error or problem in the IDE invocation code

ODI-1502
Load plan instance {0} is in an inconsistent state: {1}

Category:
Other

Cause:
Indicates a problem in the ODI code, like a wrapped IllegalStateException

Action:
null

ODI-1503
Load plan logs for instance {0}, run {1} are corrupted: {2}

Category:
Other

Cause:
Indicates a problem in the ODI code, it is a wrapped IllegalStateException

Action:
null

ODI-1504
Trying to update variables during execution of step "{0}" (load plan instance {1}, run {2}), as part of the exception handler for step "{3}", but variable updates during exception handlers are not supported.

Category:
Other

Cause:
null

Action:
null

ODI-1505
Current value "{0}" of variable "{1}" (while evaluating When clause "{2}") is not a valid value of type {3} (load plan instance {4}, run {5}).

Category:
Other

Cause:
null

Action:
null

ODI-1506
"Comparison value of step "{2}" ("{0}") is not a valid value of type {3} (load plan instance {4}, variable tested "{1}").

Category:
Other

Cause:
null

Action:
null

ODI-1507
Load Plan Instance restart called for instance {0}, but no previous runs were found.

Category:
Other

Cause:
null

Action:
null

ODI-1508
Load Plan Instance start called for instance {0}, but previous runs have been found.

Category:
Other

Cause:
null

Action:
null

ODI-1509
Load Plan Instance {0} cannot be restarted because the previous run ({1}) status "{2}" is not in "{3}" status.

Category:
Other

Cause:
null

Action:
null

ODI-1510
The same load plan instance {0} simultaneously started by two agents.

Category:
Other

Cause:
null

Action:
null

ODI-1511
Step "{0}" should have already been marked as started before adding value for variable "{1}" (load plan instance {2}, run {3}).

Category:
Other

Cause:
null

Action:
null

ODI-1512
Variable "{0}" is defined as having datatype "{1}" in Load Plan instance {2}, but as having type "{3}" in scenario "{4}" (version {5}), Load Plan instance step "{6}".

Category:
Other

Cause:
null

Action:
null

ODI-1513
Error reading load plan information for session number {0}: "{1}"

Category:
Other

Cause:
null

Action:
null

ODI-1514
Error trying to stop load plan, instance {0} not found.

Category:
Other

Cause:
null

Action:
null

ODI-1515
Load Plan instance {0} could not be stopped by agent {1} because stop type ({2}) provided in the request is invalid.

Category:
Other

Cause:
null

Action:
null

ODI-1516
Can not start load plan: load plan with name "{0}" does not exist in work repository {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1517
Load Plan instance {0}, run {1} could not be stopped because that run is already completed (with status "{2}").

Category:
Other

Cause:
null

Action:
null

ODI-1518
Parallel step "{0}" failed; {1} child step(s) in error, which is more than the maximum number of allowed errors ({3}) defined for the parallel step. Failed child steps: {2}

Category:
Other

Cause:
null

Action:
null

ODI-1519
Serial step "{0}" failed because child step "{1}" is in error.

Category:
Other

Cause:
null

Action:
null

ODI-1520
Case-When/Else step "{0}" failed because child step "{1}" is in error.

Category:
Other

Cause:
null

Action:
null

ODI-1521
Case step "{0}" failed; the selected child "{1}" is in error.

Category:
Other

Cause:
null

Action:
null

ODI-1522
Run Scenario step failed during invocation. Error message was: {0}

Category:
Other

Cause:
null

Action:
null

ODI-1523
Exception handler for step "{0}" failed, because the root exception serial step "{1}" is in error.

Category:
Other

Cause:
null

Action:
null

ODI-1524
Physical agent {0} could not be found.

Category:
Other

Cause:
null

Action:
null

ODI-1525
Physical agent not found for logical agent name "{0}" and context "{1}" while executing step "{2}".

Category:
Other

Cause:
null

Action:
null

ODI-1526
Error encountered while trying to start scenario "{1}{2}" (step "{3}"): {0}

Category:
Other

Cause:
null

Action:
null

ODI-1527
Error refreshing variable "{0}": the associated SQL query returned no results.

Category:
Other

Cause:
null

Action:
null

ODI-1528
Error refreshing variable "{0}": {1}

Category:
Other

Cause:
null

Action:
null

ODI-1529
Refresh of variable "{0}" failed : {1} {2}

Category:
Other

Cause:
null

Action:
null

ODI-1530
Load plan instance was stopped by user request.

Category:
Other

Cause:
null

Action:
null

ODI-1531
Timeout triggered while executing step "{0}".

Category:
Other

Cause:
null

Action:
null

ODI-1532
Timeout triggered on a parent step "{0}" while executing step "{1}".

Category:
Other

Cause:
null

Action:
null

ODI-1533
Error refreshing variable "{0}": could not get a connection to the logical schema "{1}" using context {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1534
Could not get SQL query text for variable "{0}" while trying to refresh it.

Category:
Other

Cause:
null

Action:
null

ODI-1535
Can not continue load plan instance {0}, run {1}, because the instance has been deleted.

Category:
Other

Cause:
null

Action:
null

ODI-1536
Load plan instance {0}, run {1} failed to launch scenario: scenario {2} does not exist in work repository {3}.

Category:
Other

Cause:
null

Action:
null

ODI-1537
Load plan instance {0}, run {1} failed to launch scenario: Version {3} of scenario {2} does not exist in work repository {4}.

Category:
Other

Cause:
null

Action:
null

ODI-1538
Unexpected Exception occurred while executing Load plan instance {0}, run {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1539
Agent {0} cannot continue load plan processing for instance {1}, run {2} on work repository {3}.

Category:
Other

Cause:
null

Action:
null

ODI-1540
Agent {0} start failure: error while trying to use Http Port {1}.

Category:
Other

Cause:
Http service was unable to use the given port.

Action:
Specify a different port by using the command-line parameter PORT.

ODI-1541
Load Plan start failure on agent {0}: ODI User and Password not specified.

Category:
Other

Cause:
ODI user and password are not set.

Action:
Please specify ODI user and password.

ODI-1542
Start Scenario failure on agent {0}: ODI User and Password not specified.

Category:
Other

Cause:
ODI User and password are not set.

Action:
Please specify ODI user and password.

ODI-1543
RuntimeAgent cannot be used inside an opened transaction, it must be used outside a TransactionTemplate

Category:
Other

Cause:
null

Action:
null

ODI-1544
None of the agents in Load Balancing list is able to handle this execution ({0}).

Category:
Other

Cause:
null

Action:
null

ODI-1545
Missing odi supervisor credentials in credential store map [{0}] with key [{1}].

Category:
Other

Cause:
Could not retrieve information from the credential store map.

Action:
Verify that the credentials have been entered correctly into the credential store map.

ODI-1546
The dbms_lock acquisition with lock handle {0} timed out.

Category:
Other

Cause:
null

Action:
null

ODI-1547
The Agent detected deadlock on dbms_lock acquisition with lock handle {0}.

Category:
Other

Cause:
null

Action:
null

ODI-1548
The dbms_lock acquisition failed with illegal lock handle {0}.

Category:
Other

Cause:
null

Action:
null

ODI-1549
The dbms_lock acquisition with lock handle {0} failed with illegal params error. The parameters are {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1550
The dbms_lock acquisition with lock handle {0} failed with unknown return code {1}

Category:
Other

Cause:
null

Action:
null

ODI-1551
The dbms_lock acquisition failed with a sql exception {0}. Please check if the work repository db user {1} has EXECUTE privilege on DBMS_LOCK package.

Category:
Other

Cause:
null

Action:
null

ODI-1552
The dbms_lock release failed with illegal lock handle {0}.

Category:
Other

Cause:
null

Action:
null

ODI-1553
The dbms_lock release for lock handle {0} failed with invalid parameters.

Category:
Other

Cause:
null

Action:
null

ODI-1554
The dbms_lock release for lock handle {0} failed because you do not own the lock.

Category:
Other

Cause:
null

Action:
null

ODI-1555
The dbms_lock release for lock handle {0} failed with an unknown return code {1}.

Category:
Other

Cause:
null

Action:
null

ODI-1556
The lock acquisition failed. The lock is already locked by other connection object.

Category:
Other

Cause:
null

Action:
null

ODI-1557
Error refreshing variable "{0}": the associated SQL query returned a NULL value.

Category:
Other

Cause:
null

Action:
null

ODI-1558
The session {0} corresponding to the load plan step {1} of load plan instance {2}, run {3} is not found. We assume this step to be in error status.

Category:
Other

Cause:
null

Action:
null

ODI-1559
Load Plan Instance {0} cannot be restarted because the context {1} was not found in the work repository {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1560
Load Plan {0} cannot be started because the context {1} was not found in the work repository {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1561
Load Plan {0} cannot be started because the user {1} does not have view privileges to the execution context {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1562
Load Plan Instance {0} cannot be restarted because the user {1} does not have view privileges to the execution context {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1563
Load Plan {0} cannot be started because the user {1} does not have execute privileges to the Load Plan {0}.

Category:
Other

Cause:
null

Action:
null

ODI-1564
Load Plan Instance {0} cannot be restarted because the user {1} does not have restart privileges.

Category:
Other

Cause:
null

Action:
null

ODI-1565
Load Plan {0} cannot be started because an unknown exception occurred.

Category:
Other

Cause:
null

Action:
null

ODI-1566
Load Plan Instance {0} cannot be restarted because an unknown exception occurred.

Category:
Other

Cause:
null

Action:
null

ODI-1567
Load Plan {0} cannot be started because a SQL Exception occurred.

Category:
Other

Cause:
null

Action:
null

ODI-1568
Load Plan Instance {0} cannot be restarted because a SQL Exception occurred.

Category:
Other

Cause:
null

Action:
null

ODI-1569
Error trying to stop load plan, instance {0} run {1} not found.

Category:
Other

Cause:
null

Action:
null

ODI-1570
Load Plan Instance {0}, run {1} cannot be stopped by Agent {2} because User {3} does not have privileges to stop the Load Plan Instance.

Category:
Other

Cause:
null

Action:
null

ODI-1571
Load Plan Instance {0}, run {1} cannot be stopped by Agent {2} because User {3} does not have privileges to stop Sessions.

Category:
Other

Cause:
null

Action:
null

ODI-1572
Load Plan Instance {0}, run {1} cannot be stopped by Agent {2} because a SQL Exception occurred while accessing the Repository.

Category:
Other

Cause:
null

Action:
null

ODI-1573
Load Plan Instance {0}, run {1} cannot be stopped by Agent {2} because an Unknown error has occurred.

Category:
Other

Cause:
null

Action:
null

ODI-1574
Day of week is not specified for the schedule.

Category:
Other

Cause:
null

Action:
null

ODI-1575
Invalid value specified for the excluded days of month filter: {0}

Category:
Other

Cause:
null

Action:
null

ODI-1576
LoadPlan Operation {0} on Agent {1} failed with the exception {2}.

Category:
Other

Cause:
null

Action:
null

ODI-1577
Parallel step error triggered on a parent step "{0}" while executing step "{1}".

Category:
Other

Cause:
null

Action:
null

ODI-1578
Invalid load plan log level value specified: {0}. A valid load plan log value is between {1} and {2}.

Category:
Other

Cause:
Invalid load plan log level value was supplied in the request.

Action:
Check that the load plan log level value supplied was valid (1 - 6) for the request.

ODI-1579
Agent {0} start failure: data source for master repository did not contain a master repository using JDBC URL={1} with USER={2}.

Category:
Other

Cause:
The master repository connection information pointed to a database schema that did not contain a master repository.

Action:
Verify the master repository connection information.

ODI-1580
Unable to set the role OWB_USER for this user.

Category:
Other

Cause:
An attempt was made to set the role OWB_USER for the connected user.

Action:
Check that the role exists and the connected user is an OWB user.

ODI-1581
Unable to set the workspace {0} for this user.

Category:
Other

Cause:
An attempt was made to select the OWB workspace for the connected user.

Action:
Check that the workspace exists and the connected user has got privilege to access it.

ODI-1582
Unexpected error when connecting to Owb workspace {0}.

Category:
Other

Cause:
An unexpected error occurred when connecting to workspace.

Action:
Verify that the Owb repository is up and running.

ODI-1583
Owb workspace {0} does not contain components that enable execution from Odi.

Category:
Other

Cause:
A component that is required by ODI has not been found in this workspace.

Action:
Verify that the Owb repository contains the correct patch for ODI.

ODI-1584
Mandatory parameter {0} is missing for https protocol.

Category:
Other

Cause:
A parameter that is required to start ODI agent to enable https protocol is missing.

Action:
Verify that the parameter is specified in odiparams.[sh|bat].

ODI-1585
A Step with Id {0} does not exist in the Session {1}

Category:
Other

Cause:
null

Action:
null

ODI-1586
A Task with Id {0} does not exist in the step {1} of the Session {2}

Category:
Other

Cause:
null

Action:
null

ODI-1587
An execution context cannot be determined for OGG operation {0}.

Category:
Other

Cause:
An execution context cannot be determined for OGG operation.

Action:
null

ODI-1588
The specified operation {0} provided is not supported by this tool.

Category:
Other

Cause:
The operation provided is not supported by this tool.

Action:
Verify the parameters

ODI-1589
The execution of the OdiOggCommand operation {0} failed.

Category:
Other

Cause:
The execution of the OdiOggCommand operation failed.

Action:
null

ODI-1590
The execution of the script failed. {0}

Category:
Other

Cause:
The execution of the script failed in the BSF Engine.

Action:
null

ODI-1591
The ODI agent name {0} specified in the client request does not match with the ODI agent {1} serving the request.

Category:
Other

Cause:
The client and the agent are not using the same physical agent name.

Action:
Verify the client and the agent are using the same agent name. Verify that the client is calling the correct agent.

ODI-1592
Error occurred testing connection to dataserver with agent {0}

Category:
Other

Cause:
Dataserver connection test failed on the agent

Action:
Verify that dataserver connection configuration is valid. Verify that dataserver is available

ODI-1593
The following bind parameters ({0}) in the task command {1} are not bound to any value. All the bind parameters should be bound for the command to be successful.

Category:
Other

Cause:
Either the source command is not providing values for some of the bind parameters in target command or the Odi Variables and/or Odi Sequence meta-data is not generated for the Scenario.

Action:
Verify that either the source command is correct or the Odi Variables and/or Odi Sequences meta-data is generated in the Scenario.

ODI-1594
The connection to the data server {0} failed.

Category:
Other

Cause:
The data server might be down or the data server connectivity settings are not correct.

Action:
Verify that you are able to test the data server using the Studio successfully.

ODI-1595
The command script failed with trace {0}.

Category:
Other

Cause:
There was a failure in the Ftp or Sftp command script.

Action:
Verify the trace and resolve the error in the command script passed to the tool.

ODI-1596
Failed to execute the pig script.

Category:
Other

Cause:
There was a failure in executing Pig script.

Action:
Verify the trace and resolve the error in the command script passed.

ODI-1597
The submitted pig script is empty.

Category:
Other

Cause:
The command did not contain or generate any pig script.

Action:
Verify the trace and resolve the error in the code generation.

ODI-1598
Failed to call method {0}.

Category:
Other

Cause:
Invocation Error.

Action:
Verify the trace and resolve the error in the runtime pig engine.

ODI-1599
The associated Dataserver with ID- {0} is missing for DataServer- {1} from topology.

Category:
Other

Cause:
Repository Error.

Action:
Verify the dataservers in topology and associate a Dataserver to current Dataserver.

ODI-1600
Unable to update Opmn Xml file.

Category:
Files

Cause:

Action:

ODI-1601
Unable to parse Opmn xml file

Category:
Files

Cause:

Action:

ODI-1602
Please provide all arguments

Category:
Other

Cause:

Action:

ODI-1603
Syntax: java DeleteAgentFromOpmn <Instance Home> <OracleOpmnHome> <Agent Name>

Category:
Other

Cause:

Action:

ODI-1604
Unable to parse Opmns Snippet Xml

Category:
Other

Cause:

Action:

ODI-1605
Component already exists in the file.

Category:
Files

Cause:

Action:

ODI-1606
Please provide the value for {0}

Category:
Other

Cause:

Action:

ODI-1607
Error reading file

Category:
Files

Cause:

Action:

ODI-1608
No of values provided for component name and port number are not equal. Please provide the same no of values for both.

Category:
Other

Cause:

Action:

ODI-1609
No of values provided for component name and JMXport number are not equal. Please provide the same no of values for both.

Category:
Other

Cause:

Action:

ODI-1610
ODI environment variable {0} is not set and ODI Tool startcmd not launched from interactive console.

Category:
Other

Cause:

Action:

ODI-1611
Must provide username for {0} before obtaining password.

Category:
Other

Cause:

Action:

ODI-1612
Unknown parameter ignored: {0}

Category:
Other

Cause:

Action:

ODI-1613
Unknown parameter value pair ignored: {0}={1}

Category:
Other

Cause:

Action:

ODI-1614
{0} is a mandatory parameter

Category:
Other

Cause:

Action:

ODI-1615
DESCRIPTION Resumes an execution session. See Oracle Data Integrator documentation for the detailed syntax. SYNTAX restartsession.(cmd|sh) "-INSTANCE=<instance_name>" <session_number> [<log_level>] ["-AGENT_URL=<agent_url>" | "-AGENT_NAME=<physical_agent_name>"]

Category:
Other

Cause:

Action:

ODI-1616
DESCRIPTION Starts an agent. See Oracle Data Integrator documentation for the detailed syntax. SYNTAX agent.(cmd|sh) -NAME=<agent name> [-PORT=<port>] [-PROTOCOL=<protocol>] [-JMXPORT=<jmxport>] [-ODI_CONNECTION_RETRY_COUNT=<nn>] [-ODI_CONNECTION_RETRY_DELAY=<nn>] PORT represents the listening port. It should match the port value specified against the physical agent defined in Topology. PROTOCOL represents the listening protocol, HTTP or HTTPS. Its default value is HTTP. NAME represents the name of this physical agent. It should match the name of a physical agent defined in Topology. User must have created an agent with this name using configuration wizard. JMXPORT represents the JMX port used for JMX notifications etc. Its default value is calculated as PORT + 1000, or 20810 if the calculated value is greater than 65535 ODI_CONNECTION_RETRY_COUNT represents the number of times a connection to the ODI Repository will be retried. Its default value is 10 ODI_CONNECTION_RETRY_DELAY represents the number of milliseconds between connection retries to the ODI Repository. Its default value is 7000

Category:
Other

Cause:

Action:

ODI-1617
DESCRIPTION Stops an agent. See Oracle Data Integrator documentation for the detailed syntax. SYNTAX agentstop.(cmd|sh) "-NAME=<agent name>" ["-AGENT_URL=<agent_url>"] ["-IMMEDIATE=<true(default)|false>" ["-MAX_WAIT=<stop timeout in millis>"]]

Category:
Other

Cause:

Action:

ODI-1618
DESCRIPTION Restarts execution of a load plan instance. See Oracle Data Integrator documentation for the detailed syntax. SYNTAX restartloadplan.(cmd|sh) "-INSTANCE=<instance_name>" <load_plan_instance_id> [<log_level>] "-AGENT_URL=<agent_url>" ["-SYNC=(no|yes)"] ["-POLLINT=<msec>"]

Category:
Other

Cause:

Action:

ODI-1619
DESCRIPTION Starts a Oracle Data Integrator command. See Oracle Data Integrator documentation for the detailed syntax. SYNTAX startcmd.(cmd|sh) "-INSTANCE=<instance_name>" <Command Name> ["<command parameter>"]*

Category:
Other

Cause:

Action:

ODI-1620
DESCRIPTION Starts a load plan. See Oracle Data Integrator documentation for the detailed syntax. SYNTAX startloadplan.sh "-INSTANCE=<instance_name>" <load_plan_name> <context_code> [<log_level>] "-AGENT_URL=<agent_url>" ["-SYNC=(no|yes)"] ["-POLLINT=<msec>"] ["-KEYWORDS=<keywords>"] ["<variable>=<value>"]*

Category:
Other

Cause:

Action:

ODI-1621
DESCRIPTION Starts a scenario. See Oracle Data Integrator documentation for the detailed syntax. SYNTAX startscen.(cmd|sh) "-INSTANCE=<instance_name>" <scenario_name> <scenario_version> <context_code> [<log_level>] ["-SESSION_NAME=<session_name>"] ["-KEYWORDS=<keywords>"] ["-AGENT_URL=<agent_url>"] ["-ASYNC=(no|yes)"] ["-DEBUGGABLE=(no|yes)"] ["-SUSPEND_FIRST_STEP=(no|yes)"] ["-DESCENDANTS_DEBUGGABLE=(no|yes)"] ["-BREAK_ON_ERROR=(no|yes)"] ["<variable>=<value>"]* -ASYNC=no is default; -ASYNC=yes is valid only if -AGENT_URL is specified.

Category:
Other

Cause:

Action:

ODI-1622
DESCRIPTION Stops a load plan instance execution. See Oracle Data Integrator documentation for the detailed syntax. SYNTAX stoploadplan.(cmd|sh) "-INSTANCE=<instance_name>" <load_plan_instance_id> [<load_plan_run_count>] "-AGENT_URL=<agent_url>" ["-STOP_LEVEL=<normal(default)|immediate>"]

Category:
Other

Cause:

Action:

ODI-1623
DESCRIPTION Stops the execution of a running session. See Oracle Data Integrator documentation for the detailed syntax. SYNTAX stopsession.(cmd|sh) "-INSTANCE=<instance_name>" <session_number> ("-AGENT_URL=<agent_url>" | "-AGENT_NAME=<physical_agent_name>") ["-STOP_LEVEL=<normal(default)|immediate>"]

Category:
Other

Cause:

Action:

ODI-1624
DESCRIPTION Encode a password. See Oracle Data Integrator documentation for the detailed syntax. SYNTAX encode.(cmd|sh) "-INSTANCE=<instance_name>" <password>

Category:
Other

Cause:

Action:

ODI-1625
This must be executed from a domain. System property domain.home cannot be null"

Category:
Other

Cause:

Action:

ODI-1626
"Neither parameter {0} nor {1} is specified"

Category:
Other

Cause:

Action:

ODI-1627
"Error getting instance properties"

Category:
Other

Cause:

Action:

ODI-1628
{0} (arg[{1}]) "{2}" should not be blank.

Category:
Other

Cause:

Action:

ODI-1629
{0} (arg[{1}]) "{2}" should specify a valid integer.

Category:
Other

Cause:

Action:

ODI-1630
{0} (arg[{1}]) "{2}" should specify a valid long number.

Category:
Other

Cause:

Action:

ODI-1631
-STOP_LEVEL parameter value must be one of: {0}, {1}

Category:
Other

Cause:

Action:

ODI-1632
Session "{0}" is being stopped ({1})

Category:
Other

Cause:

Action:

ODI-1633
OracleDI: Starting scenario {0} {1} in context {2} ...

Category:
Other

Cause:

Action:

ODI-1634
"Either parameter {0} or {1} should be specified, and they cannot be specified together."

Category:
Other

Cause:

Action:

ODI-1635
"Debug parameters are ignored when -AGENT_NAME parameter is specified."

Category:
Other

Cause:

Action:

ODI-1650
-AGENT_URL=<agent_url> is a mandatory parameter

Category:
Other

Cause:

Action:

ODI-1651
Agent {0} error while executing: {1}

Category:
Other

Cause:

Action:

ODI-1652
Unknown parameter ignored: {0}

Category:
Other

Cause:

Action:

ODI-1653
Unknown parameter value pair ignored: {0}={1}

Category:
Other

Cause:

Action:

ODI-1654
load_plan_instance_id is a mandatory parameter

Category:
Other

Cause:

Action:

ODI-1655
Usage: RestartLoadPlan -INSTANCE=<instance_name> <load_plan_instance_id> [<log_level>] "-AGENT_URL=<agent_url>" ["-SYNC=(no|yes)"] ["-POLLINT=<msec>"]

Category:
Other

Cause:

Action:

ODI-1656
Load plan instance "{0}", run {1} has restarted

Category:
Other

Cause:

Action:

ODI-1657
load_plan_name and context_code are mandatory parameters

Category:
Other

Cause:

Action:

ODI-1658
Usage: StartLoadPlan -INSTANCE=<instance_name> <load_plan_name> <context_code> [<log_level>] "-AGENT_URL=<agent_url>" ["-SYNC=(no|yes)"] ["-POLLINT=<msec>"] ["-KEYWORDS=<keywords>"] ["<variable>=<value>"]*

Category:
Other

Cause:

Action:

ODI-1659
Load plan "{0}", instance "{1}", run {2} has started

Category:
Other

Cause:

Action:

ODI-1660
load_plan_instance_id is a mandatory parameter

Category:
Other

Cause:

Action:

ODI-1661
Usage: StopLoadPlan -INSTANCE=<instance_name> <load_plan_instance_id> [<load_plan_run_count>] "-AGENT_URL=<agent_url>" [-STOP_LEVEL=<normal (default) | immediate>]

Category:
Other

Cause:

Action:

ODI-1662
Load plan instance "{0}", run {1} has stopped ({2})

Category:
Other

Cause:

Action:

ODI-1663
-STOP_LEVEL parameter value must be one of: {0}, {1}

Category:
Other

Cause:

Action:

ODI-1664
Waiting for completion of load plan execution.

Category:
Other

Cause:

Action:

ODI-1665
Load plan execution completed in {0} status.

Category:
Other

Cause:

Action:

ODI-1700
SessionId is not valid

Category:
Other

Cause:

Action:

ODI-1701
The session was not found in the repository: {0}

Category:
Other

Cause:

Action:

ODI-1702
This operation is not supported on this platform

Category:
Other

Cause:

Action:

ODI-1800
Exception {0} has occurred as ESS-EM linking is disabled.

Category:
Configuration

Cause:
Unable to connect to master repository.

Action:
Check if the master repository is accessible and up. This is not mandatory since master repositories can be down.

ODI-1801
Agent target discovery mbean registration has failed due to {0}.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error and take corrective action.

ODI-1802
Agent target discovery mbean unregistration has failed due to {0}.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error and take corrective action.

ODI-1803
Error {0} has occurred during mbean registration.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error.

ODI-1804
Error {0} has occurred during mbean deregistration.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error.

ODI-1805
Error {0} has occurred during notification listener registration.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error.

ODI-1806
Error {0} has occurred during notification listener deregistration.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error.

ODI-1807
Error {0} has occurred during deregistration of ODI Service Mbean {1}.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error.

ODI-1808
Error {0} has occurred during registration of Agent Service Mbean.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error, fix the server and restart the OdiConsole application.

ODI-1809
Error {0} has occurred during registration of Master Repository Service Mbean.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error, fix the error and restart the OdiConsole application.

ODI-1810
Error {0} has occurred during registration of Work Repository Service Mbean.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error, fix the error and restart the OdiConsole application.

ODI-1811
Error {0} has occurred during registration of Session Service Mbean.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error, fix the error and restart the OdiConsole application.

ODI-1812
Error {0} has occurred during registration of Event Service Mbean.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error, fix the error and restart the OdiConsole application.

ODI-1813
Error {0} has occurred during registration of Session Search Service Mbean.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error, fix the error and restart the OdiConsole application.

ODI-1814
No repository definition found for work repository {0} in repositories.xml. Search will be disabled for this repository.

Category:
Configuration

Cause:
A configuration error has occurred.

Action:
Add the jndi entries for all the work repositories for each of the master repositories in repositories.xml.

ODI-1815
Exception {0} has occurred during Session Search by id.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
No action is required. The session id mentioned for search is not available.

ODI-1816
Session status passed {0} is invalid.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error.

ODI-1817
Error {0} has occurred while fetching statistics for agents. Statistics shown might not be complete.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error.

ODI-1818
Agent Service Mbean is not initialized. Re-initialization of agents in tree is disabled.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error, fix the same and restart the OdiConsole application.

ODI-1819
Event Service Mbean is not initialized. Re-initialization of event notification listeners is disabled.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check log for details on the error, fix the same and restart the OdiConsole application.

ODI-1820
Agent {0} is not up at {1} for reason {2}.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error.

ODI-1821
JMXConnector failed to provide MBean server connection.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error.

ODI-1822
Error occured while closing JMXConnector.

Category:
Programmatic

Cause:
A runtime error has occurred.

Action:
Check the log for details on the error.

ODI-3000
error in creating repository connection {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3001
error in updating repository connection {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3002
error in deleting repository connection {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3003
Failed to connect to the error table {0}. Check the connection details and retry.

Category:
Programmatic

Cause:
The table might no longer exist or the structure of the table might not be correct.

Action:
Check the connection details and retry.

ODI-3016
Creation of Work Repository failed because a previous Work repository was found, and the user had asked not to overwrite any existing repository.

Category:
Data

Cause:
Work repository already exists and overwriting of the repository was not chosen

Action:
Select overwriting of Work Repository

ODI-3017
Exception occurred while creating Work Repository at {0} failed. Failure reason {1}.

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3018
Test connection failed due to {0}.

Category:
Data

Cause:
Connection to DB failed

Action:
Check the logs.

ODI-3019
Exception occurred while exporting Master Repository. Failure reason {0}.

Category:
Data

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3020
Only zip files can be uploaded , the {0} upload was unsuccessful.

Category:
Data

Cause:
A file with extension other than zip was uploaded.

Action:
Make sure file uploaded has zip as extension

ODI-3021
Exception occurred while importing Work Repository. Failure reason {0}.

Category:
Data

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3022
Attaching of Work Repository failed due to error: {2}

Category:
Programmatic

Cause:
Errored out due to {2} and overwriting of the repository was not chosen

Action:
Check the logs

ODI-3023
Attaching of Work Repository failed

Category:
Programmatic

Cause:
An unexpected error occured and overwriting of the repository was not chosen

Action:
Check the logs

ODI-3024
Exception occurred while attaching Work Repository at {0} failed. Failure reason {1}.

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3031
Creation of Master Repository failed at {0}.

Category:
Data

Cause:
Creation of Master Repository Failed

Action:
Check the logs.

ODI-3032
Exception occurred while creating Master Repository at {0} failed. Failure reason {1}.

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3033
Supervisor Password and Confirm Supervisor Password fields should match.

Category:
Data

Cause:
Supervisor Password and Confirm Supervisor Password fields must match

Action:
Input same passwords

ODI-3034
Test connection failed due to {0}.

Category:
Data

Cause:
Testing of DB connection failed

Action:
Check the logs

ODI-3035
Supervisor Password and Confirm Supervisor Password fields should match and only zip files can be uploaded , the {0} upload was unsuccessful.

Category:
Data

Cause:
Both the password match and zip files to be uploaded conditions failed

Action:
Make sure both the passwords are same and file uploaded is zip file

ODI-3036
Only zip files can be uploaded , the {0} upload was unsuccessful.

Category:
Data

Cause:
zip files to be uploaded condition failed

Action:
Make sure file uploaded is zip file

ODI-3037
Exception occurred while exporting Master Repository. Failure reason {1}.

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3038
Exception occurred while exporting Physical Topology. Failure reason {1}.

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3039
Exception occurred while Importing Master Repository. Failure reason {1}.

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3040
Unable to connect to the Repository User. {0}

Category:
Data

Cause:
Testing of DB connection failed

Action:
Check the logs

ODI-3041
Unable to connect to the DBA User. {0}

Category:
Data

Cause:
Testing of DB connection failed

Action:
Check the logs

ODI-3046
unable to find the agent for given logical agent and context code

Category:
Data

Cause:
Physical Agent mapping was not defined for selected logical agent and context.

Action:
A different set of credentials is required or the mapping needs to be defined.

ODI-3047
exception while executing {0}. Failure reason {1}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3048
Only XML files can be uploaded: the {0} upload fails

Category:
Data

Cause:
File selected for import was not a XML file.

Action:
Provide the XML file.

ODI-3049
exception while importing {0}. Failure reason {1}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3050
failed to start scenario : {0} ? {1} in debug mode.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3075
Error in purging Load Plans Executions/Sessions {0}

Category:
Programmatic

Cause:
An exception has occurred.

Action:
Check the logs.

ODI-3076
exception while killing {0}. Failure reason {1}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3077
Selected Session {0} is in {1} State, and therefore cannot be killed.

Category:
Data

Cause:
The selected session was in Done, Error, or Warning state.

Action:
No action is required.

ODI-3078
Selected Session {0} is in {1} State, and therefore cannot be restarted.

Category:
Data

Cause:
The selected session was not in Error state.

Action:
No action is required.

ODI-3079
exception while restarting {0}. Failure reason {1}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3080
exception while clearing stalesessions. Failure reason {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3081
Error fetching records from error table {0}. The table might no more exist or the format of the table is not correct

Category:
DATA

Cause:
The table might no longer exist or the structure of the table might not be correct

Action:
Upgrade the CKM

ODI-3082
CKM SQL does not contain ODI_PK primary key column. Hence unable to delete the error records.

Category:
Programmatic

Cause:
CKM SQL does not contain ODI_PK primary key column. Hence unable to delete the error records.

Action:
Future release will have the ODI_PK primary key column incorporated in CKM SQL.

ODI-3083
Scenario "{0}" parent not found.

Category:
Data

Cause:
Trying to get the Odi Object which does not exist or has been deleted.

Action:
Check the logs

ODI-3090
failed to restart session : {0} in debug mode.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3101
import of {1} from {0) failed

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3102
export of {1} to {0) failed

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3103
failed to stop a loadplan instance id : {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3104
failed to start a loadplan : {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3105
failed to start a scenario : {0} ? {1}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs1

ODI-3106
failed to restart session : {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3107
failed to clean stale sessions for repository : {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3108
failed to stop session : {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3109
Creation of work runtime repository at {0} failed. Failure reason {1}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3110
Update of work runtime repository at {0} failed. Failure reason {1}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3111
failed to read config.properties

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3112
shared config dir path is not valid : {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3114
{0} not set

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3115
{0} is not correct

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3116
failed to read

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3117
datasource not located at {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3118
Could not get the service locator. JpsServiceLocator service is not configured.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3119
JPS Exception {0} was thrown. Credential Store might not be configured.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3120
Credential store could not be found.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3121
Not populating any values in credential store

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3122
Exception in purging Session/Load Plan Executions

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3123
Exception occured while inserting usedInContext in Physical Schema

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3124
Exception occured while deleting usedInContext in Physical Schema

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3125
Exception occured while inserting usedInContext in Edit Physical Schema

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3126
Exception in adding an entity

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3127
Odi object not found

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3128
Exception in update

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3129
Unable to find odi object {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3130
Loading of entity failed

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3131
Unauthorized to delete entity of type

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3132
error occurred while executing method

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3133
no repository definition found for alias {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3134
login failed for user {0}=

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3135
version mismatch

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3136
unable to connect to repository with alias {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3137
Error occurred in EMIntegrationServlet.doOperation() - {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3138
failed to init jview diagrammer

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3139
repositories.xml path not set

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3140
{0} file does not exist at {1}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3141
failed to create RepositoryDefinitionRegistry

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3142
error logging out a user after session expired

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3143
Creation of work dev repository at {0} failed. Failure reason {1}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3144
Creation of Master Repository failed at {0}. Failure reason {1}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3145
Check the logsPrivilegedActionException {0} was thrown. system-jazn-data.xml might not have the privileges specified.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3146
???

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3147
Delete operation failed

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3148
Maximum number of sessions should be in between 1 and 99999.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3149
Port Number should not be non negative.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3150
Invalid Context code. Context code cannot have lower case characters and white spaces. Though, it can contain '$' and '_' special characters.

Category:
Programmatic

Cause:
A validation error occured

Action:
Context code cannot have lower case characters and white spaces

ODI-3184
Maximum Cache Entries cannot be less than zero.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3185
Unused Blueprint Lifetime cannot be less than zero.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3186
Maximum Threads Number cannot be less than Max Threads Per Session.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3187
Max Threads Per Session cannot be less than zero.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3188
Maximum Threads Number should be greater than zero.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3189
Maximum Threads Number cannot be less than Maximum Session Number.

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3190
Exception fetching connector points. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3191
Exception fetching model. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3192
Exception fetching physical schema. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3193
Exception fetching Data Server. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3194
Exception fetching Catalog. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3195
Exception fetching Constraints. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3196
Exception fetching connector point properties. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3197
Exception during Hadoop Initialization. Reason: {0}

Category:
Programmatic

Cause:
Error occurred.

Action:
Check the logs.

ODI-3198
Exception during Oozie Initialization. Reason: {0}

Category:
Programmatic

Cause:
Error occurred.

Action:
Check the logs.

ODI-3199
Failed to initiate Log retriever. Reason: {0}

Category:
Programmatic

Cause:
Error occurred.

Action:
Check the logs.

ODI-3200
Invalid Deployment Archive. Reason: {0}

Category:
Programmatic

Cause:
Error occurred.

Action:
Check the logs.

ODI-3201
Exception viewing Deployment Archive. Reason: {0}

Category:
Programmatic

Cause:
Error occurred.

Action:
Check the logs.

ODI-3202
IO Exception in Deployment Archive. Reason: {0}

Category:
Programmatic

Cause:
Error occurred.

Action:
Check the logs.

ODI-3203
Exception. Reason: {0}

Category:
Programmatic

Cause:
Error occurred.

Action:
Check the logs.

ODI-3226
Parameter File could not be Loaded.

Category:
Data

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3260
Failed to apply settings for agent: {0}

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3261
Exception while applying settings for agent: {0}. Failure reason: {1}

Category:
Programmatic

Cause:
An unexpected error occurred

Action:
Check the logs

ODI-3265
Exception occurred while creating Datasource. Failure reason {0}.

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3266
Data Source already exists for {0}.

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3267
No valid repository alias is found. Click on management link on top right corner to create one.

Category:
Data

Cause:
Either there were no repository connection aliases, or those that were created did not have a valid JNDI name

Action:
Create a new repository connection alias.

ODI-3276
Tab limit reached.Please close at least one tab.

Category:
Data

Cause:
Max limit on the number of tabs that can be open has been met.

Action:
Close at least one tab

ODI-3277
Object cannot be found.

Category:
Data

Cause:
The object might have been deleted.

Action:
Refresh your view.

ODI-3278
View operation fails with the following exception {0}. See the server log for details.

Category:
Data

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3279
Add operation failed with the following exception {0}. Please see the server log for details.

Category:
Data

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3280
Edit operation failed with the following exception {0}. Please see the server log for details.

Category:
Data

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3281
Delete operation failed with the following exception {0}. Please see the server log for details.

Category:
Data

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3290
You are not authorized to add a new entity of this type.

Category:
Data

Cause:
User doesn't have required privileges to add an new entity of a particular type

Action:
No action

ODI-3326
Please specify a valid search text

Category:
Data

Cause:
Invalid search text was specified

Action:
Provide a valid search text

ODI-3327
Please choose at least one model or project type.

Category:
Data

Cause:
No model or project type was selected

Action:
Select at least one model or project type so that search criteria is valid

ODI-3328
Please choose at least one topology type.

Category:
Data

Cause:
No topology type was selected

Action:
Select at least one topology type so that search criteria is valid

ODI-3329
Please choose at least one runtime type.

Category:
Data

Cause:
No runtime type was selected

Action:
Select at least one runtime type so that search criteria is valid

ODI-3330
Exception while importing attrbutes. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3331
Exception while importing properties. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3332
Exception while fetching attributes. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3333
Exception while fetching properties. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3334
Exception while importing propeties and expressions of attributes. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3335
Exception while loading components. Reason: {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3336
Error in persisting user preferences {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3337
UserPref.xml path is not set

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3338
Failed to get User Preferences

Category:
Programmatic

Cause:
An unexpected error occured

Action:
Check the logs

ODI-3339
Error in getting policies. Reason: {0}

Category:
Programmatic

Cause:
Error occurred.

Action:
Check the logs.

ODI-3501
Exception while applying deployment archive. Failure reason {0}

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check the logs.

ODI-3502
Invalid Credential File Password.

Category:
Data

Cause:
The password entered is not correct.

Action:
Re-enter correct credential file password.

ODI-3503
Credential File Not Accessible.

Category:
Data

Cause:
Credential File Permission

Action:
Check permission of Credential file and retry.

ODI-3504
Oracle DB Connection details not found in credential file

Category:
Data

Cause:
Oracle Database connection details not stored in credential file.

Action:
Save oracle database connection details in credential file before using.

ODI-3505
Please select credential file.

Category:
Data

Cause:
Credential file not chosen

Action:
Choose credential file.

ODI-3506
Uploading of File {0} was not successful.

Category:
Data

Cause:
File could not be uploaded.

Action:
Check network connectivity and retry.

ODI-3507
Please enter credential file password.

Category:
Data

Cause:
Credential file password not entered

Action:
Enter credential file password.

ODI-3508
Invalid Credential file.

Category:
Data

Cause:
The file chosen is not a credential file.

Action:
Choose valid credential file.

ODI-5000
Task {0} ({1}) on logical schema {2} with Context Id {3} fails since scripting technology name could not be discovered.

Category:
Other

Cause:
null

Action:
null

ODI-5001
Session {0} ({1}) could not be stopped by Agent {2}: Session run on an 'Internal' agent cannot be stopped from another process.

Category:
Other

Cause:
Stopping a session being run by an internal agent from another process is not possible.

Action:
Review the session execution details in the Operator Navigator or Repository Explorer.

ODI-5002
Pig Script Execution failure: The following {0} Job(s) - [{1}] reported failed. Please check the resource manager logs for these jobs for the failure reason.

Category:
Other

Cause:
There was a failure in executing Pig script in MapReduce Mode. Some Jobs have been reported failed.

Action:
Verify the Resource Manager trace and resolve the error in the command script passed.

ODI-5003
No associated Hadoop dataserver found for given logical schema {0}.

Category:
Other

Cause:
Repository Error.

Action:
Verify given logical schema is Hadoop dataserver or associated with Hadoop dataserver .

ODI-5004
None of the logical schemas {0} and {1} associated with Hadoop dataserver.

Category:
Other

Cause:
Repository Error.

Action:
Verify given logical schema is Hadoop dataserver or associated with Hadoop dataserver .

ODI-5005
Illegal state. Classloader not found for key: {0} for ODI task with name {1}.

Category:
Other

Cause:
ODI Script Engine Error.

Action:
As a workaround try removing classpaths from the Dataserver assocaited with the task and configure them on the agent instead.

ODI-5006
Unrecoverable OdiAgentException occurred during Load Plan execution. Unable to stop and close Load Plan execution due to exception:

Category:
Other

Cause:
null

Action:
null

ODI-5007
Authentication failed. Cannot advance loadplans without authentication. So pending advancing loadplans will be stopped and closed:

Category:
Other

Cause:
null

Action:
null

ODI-5008
Error occurred previewing file on agent {0}, as file {1} is empty

Category:
Other

Cause:
Error previewing file on the agent, as file is empty

Action:
Verify that file is not empty

ODI-5100
Agent {0} cannot read configuration. Cause: {1}.

Category:
Other

Cause:
The agent configuration cannot be read.

Action:
Review the cause and take appropriate action.

ODI-10000
Method setObject class DwgObjectRepresentor does not support object class: {0}.

Category:
Other

Cause:
Java method was not found.

Action:
Contact Oracle Support Services.

ODI-10001
Action unauthorized for this license: {0}

Category:
Security

Cause:
Action was unauthorized for this license.

Action:
Choose another license.

ODI-10002
Only one local repository can be defined; {0} were found.

Category:
Other

Cause:
More than one local repository was found.

Action:
Contact Oracle Support Services.

ODI-10003
No connection set.

Category:
Other

Cause:
No connection was set.

Action:
Set connection.

ODI-10004
File already exists.

Category:
File

Cause:
File already existed.

Action:
Choose another file.

ODI-10005
Repository is expected to be a master repository.

Category:
Other

Cause:
Repository was expected to be a master repository.

Action:
Choose master repository.

ODI-10006
Repository is expected to be enterprise repository.

Category:
Other

Cause:
Repository was expected to be an enterprise repository.

Action:
Choose enterprise repository.

ODI-10007
Object must be in editable state before using set methods.

Category:
Other

Cause:
The object was not in editable state.

Action:
Edit this object.

ODI-10008
Object must be in consult mode before using methods get.

Category:
Other

Cause:
The object was not in consult mode.

Action:
Consult the object.

ODI-10009
Object does not exist in the repository.

Category:
Other

Cause:
The repository did not contains this object.

Action:
Choose another object or create first this one.

ODI-10010
This type of object cannot be updated.

Category:
Other

Cause:
Object could not be updated.

Action:
Do not update this object.

ODI-10011
Invalid object; it has been updated by another user.

Category:
Other

Cause:
Object was updated by another user.

Action:
Refresh the object.

ODI-10012
Object cannot be inserted

Category:
Other

Cause:
Object could not be inserted.

Action:
Check object.

ODI-10013
This import action has been cancelled because it could damage your repository. This is due to an {0} object that has object identifier {1} that is greater than that for the current {0} id sequence. Importing this object would lead to primary key violations in the future.

Category:
Other

Cause:
Import could damage your repository.

Action:
Check identifier sequences.

ODI-10014
Method must be redefined in derived classes. It cannot be called for DwgObject

Category:
Other

Cause:
Method must be redefined in derived classes.

Action:
Call redefined method.

ODI-10015
The work repository {0} is not declared in this master repository, the import process has been cancelled.

Category:
Other

Cause:
Work repository was not declared in this master repository.

Action:
Declare work repository and try again.

ODI-10016
Import aborted.

Category:
Other

Cause:
Import was aborted.

Action:
Check objects and try again.

ODI-10017
This import is forbidden: the text {0} has a different origin in the repository and in the import file.

Category:
Other

Cause:
The text has a different origin in the repository and in the import file.

Action:
Check import file and try again.

ODI-10018
The repository {0} is not coherent between the current repository and the import file.

Category:
Other

Cause:
The repository was not coherent between the current repository and the import file.

Action:
Check import file.

ODI-10019
Impossible to create the directory {0}.

Category:
File

Cause:
I was not possible to create the directory.

Action:
Check your system rights for creating directory; directory's path and name.

ODI-10020
Impossible to replace the file

Category:
File

Cause:
It was not possible to replace the file.

Action:
Check, if you have enough rights for this operation.

ODI-10021
Unspecified save directory.

Category:
Other

Cause:
Directory to save environment information was unspecified.

Action:
Specify the directory for saving the environment information file.

ODI-10022
You must specify all options.

Category:
Other

Cause:
Missed one or more options.

Action:
Specify missed options.

ODI-10023
Invalid license. This license is suitable for {0}.

Category:
Security

Cause:
Invalid license.

Action:
Check license.

ODI-10024
Your installation of Oracle Data Integrator is corrupted.

Category:
Other

Cause:
The technology description file contains errors.

Action:
Reinstall Oracle Data Integrator.

ODI-10025
Your installation of Oracle Data Integrator is corrupted.

Category:
Other

Cause:
The technology description file is missing.

Action:
Reinstall Oracle Data Integrator.

ODI-10026
Error while testing the Master Repository technology.

Category:
Other

Cause:
Error occurred while testing the Master Repository technology.

Action:
Check parameters.

ODI-10027
The import is canceled because at least one object is locked by another user.

Category:
Other

Cause:
At least one object was locked by another user.

Action:
Check objects' locks.

ODI-10028
It is forbidden to import a log into a repository having the same ID.

Category:
Other

Cause:
The log had the same ID as repository.

Action:
Check log and/or repository id.

ODI-10029
Version {0} for object {1} already exists.

Category:
Other

Cause:
Version already existed.

Action:
Choose another version.

ODI-10030
DwgBeanWrapper can only wrap DwgObjects

Category:
Other

Cause:
DwgBeanWrapper can only wrap DwgObjects

Action:
Choose correct type of objects.

ODI-10031
Object {0}: {1} is locked by user {2}

Category:
Other

Cause:
Object was locked by another user.

Action:
Wait until object is unlocked.

ODI-10032
You cannot import this object ({0}). A referenced object ({1}) does not exist in the repository.

Category:
Other

Cause:
A referenced object does not exist in the repository.

Action:
Check import file.

ODI-10033
You cannot delete this object because it is locked by another user ({0}).

Category:
Other

Cause:
This object was locked by another user.

Action:
Wait until object is unlocked.

ODI-10034
The technology hosting your master repository does not support Versioning.

Category:
Other

Cause:
The technology did not support versioning.

Action:
Choose another repository or technology.

ODI-10035
{0} : "{1}" (with global id: {5} and internal id: {6}) violates alternate key constraint {2} {3} for values {4}

Category:
Other

Cause:
Object violated alternate key constraint.

Action:
Check object properties and constraint's values.

ODI-10036
Importing object {0} : {1} (with global id: {2} and internal id: {3}) failed.

Category:
Other

Cause:
Import failed.

Action:
Check import file and try again.

ODI-10037
Import-replace for this node is supported for action groups only. The import file is invalid.

Category:
Other

Cause:
Import-replace for this node was supported for action groups only.

Action:
Check import file.

ODI-10038
The interface you are trying to use ({0}) is related to a logical schema ({1}) that no longer exists.

Category:
Other

Cause:
Logical schema was not found.

Action:
Check interface.

ODI-10039
Bad ID for an object representer

Category:
Other

Cause:
Bad ID for an object representer

Action:
Check object`s ID.

ODI-10040
Cannot create directory

Category:
File

Cause:
Directory could not be created.

Action:
Check directory path/name.

ODI-10041
Oracle Data Integrator Remote Object (SnpRemoteObject) must inherit from SnpsFunction.

Category:
Other

Cause:
Oracle Data Integrator Remote Object (SnpRemoteObject) did not inherit from SnpsFunction.

Action:
Use SnpsFunction as parent.

ODI-10042
SnpsQuery must be connected prior to execution

Category:
Other

Cause:
SnpsQuery was not connected.

Action:
Set a connection.

ODI-10043
Security token is a mandatory parameter

Category:
Security

Cause:
Security token was not specified.

Action:
Check security parameters.

ODI-10044
Unable to save the interface. Maximum number of source datastores exceeded.

Category:
Other

Cause:
Maximum number of source datastores was exceeded.

Action:
Contact Oracle Support Services.

ODI-10045
a2.getCargo() not instance of SAPSegment

Category:
Other

Cause:
a2.getCargo() not instance of SAPSegment

Action:
Check SAP Tree.

ODI-10046
No IDoc.

Category:
Other

Cause:
Missed IDoc.

Action:
Check IDoc.

ODI-10047
Repository is not a development work repository

Category:
Other

Cause:
Repository was not a development work repository.

Action:
Choose development work repository.

ODI-10048
No work repository found.

Category:
Other

Cause:
No work repository was found.

Action:
Check your connection settings or database.

ODI-10049
Missing parameter

Category:
Other

Cause:
Parameter was missing.

Action:
Check all parameters.

ODI-10050
Missing parameter at: {0} SQL: {1}

Category:
Other

Cause:
Parameter was missing.

Action:
Check all parameters.

ODI-10051
Some objects cannot be exported because they do not exist in the repository: {0} {1}

Category:
Other

Cause:
Objects did not exist in the repository.

Action:
Check objects state.

ODI-10052
A problem occurred in your repository.

Category:
Other

Cause:
A problem occurred in your repository.

Action:
Contact Oracle Support Services.

ODI-10053
Problem retrieving JCOFunction object. {0}

Category:
Other

Cause:
Problem occurred retrieving JCOFunction object.

Action:
Check JCO Function object.

ODI-10054
Unable to find the XML file corresponding to your technology.

Category:
Other

Cause:
XML file corresponding to your technology was not found.

Action:
Check technology and/or XML file for the technology.

ODI-10055
This ID is already in use in the repository

Category:
Other

Cause:
This ID was already in use in the repository.

Action:
Change ID.

ODI-10056
This repository ID already exists. This repository cannot be created.

Category:
Other

Cause:
Repository ID already existed.

Action:
Change repository ID.

ODI-10057
Unrecognized export type.

Category:
Other

Cause:
Export type was unrecognized.

Action:
Check export type.

ODI-10058
You are trying to import objects from a master repository of an older version into {0} version. This action is forbidden. Master repositories must be upgraded using the upgrade assistant, not using the export/import facility.

Category:
Other

Cause:
You tried to import objects from a master repository of an older version.

Action:
Master repositories must be upgraded using the upgrade assistant, not using the export/import facility.

ODI-10059
Repository is null

Category:
Other

Cause:
Repository was null.

Action:
Check repository.

ODI-10060
Saputil is mandatory.

Category:
Other

Cause:
Saputil was mandatory.

Action:
Check Saputil

ODI-10061
Empty XML Character Set

Category:
Other

Cause:
XML Character Set was empty.

Action:
Fill XML Character Set.

ODI-10062
Unable to find license key {0}. An exception {1} occurred with message: {2}

Category:
Other

Cause:
An exception occurred.

Action:
Check license key.

ODI-10063
Unable to check the license key. An exception {0} occurred with message: {1}

Category:
Other

Cause:
An exception occurred.

Action:
Check license key.

ODI-10064
The interface must have a JMS datastore as a source or target. Another license is required otherwise.

Category:
Other

Cause:
The interface must have a JMS datastore as a source or target.

Action:
Check datastore type and/or license.

ODI-10065
You license does not include these features. Please contact your reseller.

Category:
Other

Cause:
You license does not include these features.

Action:
Please contact your reseller.

ODI-10066
The interface is using a Datastore defined in Model "{0}" which is linked to a logical schema "{1}" that no longer exists.

Category:
Other

Cause:
Logical schema was not found.

Action:
Correct interface.

ODI-10067
Target file already exists.

Category:
File

Cause:
Target file already existed.

Action:
Choose another target file name.

ODI-10068
SnpsConnection: Current Isolation level: {0}. The new Isolation level: {1}, not supported

Category:
Other

Cause:
Isolation level not supported.

Action:
Check isolation level.

ODI-10069
Unsupported XML Character Set: {0}

Category:
Other

Cause:
Unsupported XML Character Set.

Action:
Check XML charset.

ODI-10070
Cannot delete this object. It is being edited or viewed

Category:
Other

Cause:
Object was being edited or viewed.

Action:
Stop edit or view object and try again.

ODI-10071
Cannot delete this object

Category:
Other

Cause:
Could not delete this object.

Action:
Check object state.

ODI-10073
A repository already exists on this data server

Category:
Other

Cause:
A repository already existed on this data server.

Action:
Choose another data server.

ODI-10074
An object with the wrong type was given to an object representative

Category:
Other

Cause:
An object with the wrong type was given to an object representative

Action:
Check object type.

ODI-10075
An object is in an unidentified state {0}

Category:
Other

Cause:
An object is in an unidentified state.

Action:
Check object state.

ODI-10076
A collection object is the wrong class

Category:
Other

Cause:
A collection object is the wrong class.

Action:
Check collection object's class

ODI-10077
Undefined action performed on an object: {0}

Category:
Other

Cause:
An undefined action was performed on an object.

Action:
Check action and object.

ODI-10078
An object will be in an unidentified state (it is in the state "{0}" and "{1}" is currently being performed on it)

Category:
Other

Cause:
An object would have been in an unidentified state.

Action:
Check object state.

ODI-10080
Incorrect License ....

Category:
Other

Cause:
Incorrect License.

Action:
Contact your seller.

ODI-10081
You are not authorized to Insert the Object: {0}: {1} / {2}

Category:
Security

Cause:
You were not authorized to Insert the Object.

Action:
Login with user with right privileges.

ODI-10082
You are not authorized to View the Object: {0}: {1}

Category:
Security

Cause:
You were not authorized to View the Object.

Action:
Login with user with right privileges.

ODI-10083
You are not authorized to Delete the Object: {0}: {1} / {2}

Category:
Security

Cause:
You were not authorized to Delete the Object.

Action:
Login with user with right privileges.

ODI-10084
You are not authorized to Edit the Object: {0}: {1} / {2}

Category:
Security

Cause:
You were not authorized to Edit the Object.

Action:
Login with user with right privileges.

ODI-10085
You cannot consult this object

Category:
Security

Cause:
You could not consult this object.

Action:
Login with user with right privileges.

ODI-10086
You cannot edit this object

Category:
Security

Cause:
You could not edit this object.

Action:
Login with user with right privileges.

ODI-10087
You can only give Supervisor Access Privileges if you are a Supervisor.

Category:
Security

Cause:
You could only give Supervisor Access Privileges if you are a Supervisor.

Action:
Login with user with right privileges.

ODI-10088
Empty Java Character Set.

Category:
Other

Cause:
Java Character Set was empty.

Action:
Fill Java charset.

ODI-10089
You cannot modify another user"s password

Category:
Security

Cause:
You cannot modify another user"s password

Action:
Login with user with right privileges.

ODI-10090
Object {0} {1} is referenced by: {2}. Cannot remove.

Category:
Other

Cause:
Object was referenced by another one.

Action:
Check object"s references.

ODI-10091
not connected

Category:
Other

Cause:
not connected

Action:
Check connection.

ODI-10092
Some objects cannot be exported. They do not exist in the repository.

Category:
Other

Cause:
Objects did not exist in the repository.

Action:
Check objects" state.

ODI-10093
You are importing an object from another repository with the same identifier. It is forbidden.

Category:
Other

Cause:
You tried to import an object from another repository with the same identifier.

Action:
Change repository ID.

ODI-10094
Problem while computing new name.

Category:
Other

Cause:
A problem occurred while computing new name.

Action:
Try again.

ODI-10095
Exception while getting the children list

Category:
Other

Cause:
Exception while getting the children list.

Action:
Try again.

ODI-10096
Error while parsing fields

Category:
Other

Cause:
Error occurred while parsing fields.

Action:
Check fields value.

ODI-10097
Impossible to find text with ID {0} in text list.

Category:
Other

Cause:
Text was not found.

Action:
Check text ID

ODI-10098
No connection available. Check connection parameters.

Category:
Network

Cause:
No connection was available.

Action:
Check connection parameters.

ODI-10099
Object cannot be exported because the file with name {0} could not be created.

Category:
Other

Cause:
Object could not be exported because the file could not be created.

Action:
Check your system rights to write files and file name.

ODI-10100
Empty XML Version

Category:
Other

Cause:
XML version was empty.

Action:
Fill XML Version.

ODI-10101
Invalid XML Version: {0}

Category:
Other

Cause:
XML Version was invalid.

Action:
Check XML version.

ODI-10102
Alias with the name {0} already exists.

Category:
Other

Cause:
Alias already exists.

Action:
Change alias.

ODI-10103
Alias with the name {0} does not exist.

Category:
Other

Cause:
Alias does not exit.

Action:
Check alias name ant try again.

ODI-10104
File {0} is not a Smart Export file and cannot be imported by Smart Import.

Category:
Other

Cause:
Smart Export file not specified for Smart Import.

Action:
Specify a Smart Export file for importing via Smart Import.

ODI-10105
Smart Import file name cannot be null.

Category:
Other

Cause:
Smart Export file name not specified for Smart Import.

Action:
Specify a Smart Export file for importing via Smart Import.

ODI-10106
Smart Import response file name cannot be null.

Category:
Other

Cause:
Smart import response file name not specified for Smart Import.

Action:
Specify a Smart Import response file.

ODI-10107
Smart Import file {0} not found.

Category:
Other

Cause:
File does not exist.

Action:
Specify an existing Smart Export file for importing via Smart Import.

ODI-10108
Smart Import response file {0} not found.

Category:
Other

Cause:
Response file does not exist.

Action:
Specify an existing Smart Import response file.

ODI-10109
File {0} is not a valid Smart Import Response file.

Category:
Other

Cause:
File is not a valid Smart Import response.

Action:
Specify an existing Smart Import response file.

ODI-10110
{0} with the same {1} exists.

Category:
Other

Cause:
An object with the same alternative key value(s) exists.

Action:
Change the alternative key value to be unique.

ODI-10111
{0} <{1}> referenced by {2} <{3}> is missing.

Category:
Other

Cause:
A referenced object does not exist.

Action:
Either import the missing object or change to reference a different object.

ODI-10112
Project code will be changed from <{0}> to <{1}>.

Category:
Other

Cause:
The import will make a change to an existing project code.

Action:
Determine whether the change to project code is desired or not.

ODI-10113
{0} with {1} <{2}> does not exist.

Category:
Other

Cause:
A referenced object does not exist.

Action:
Either import the missing object or change to reference a different object.

ODI-10114
{0} with {1} id <{2}> does not exist.

Category:
Other

Cause:
A referenced object does not exist.

Action:
Either import the missing object or change to reference a different object.

ODI-10115
{0} with the same name <{1}> already exists.

Category:
Other

Cause:
A different object with the same name already exists.

Action:
Either change the name of the object being imported or use match by name to match to the already existing object with the same name.

ODI-10116
Model code will be changed from <{0}> to <{1}>.

Category:
Other

Cause:
The import will make a change to an existing model code.

Action:
Determine whether the change to model code is desired or not.

ODI-10117
Sub-model code will be changed from <{0}> to <{1}>.

Category:
Other

Cause:
The import will make a change to an existing sub-model code.

Action:
Determine whether the change to sub-model code is desired or not.

ODI-10118
A different Physical Schema is already set as the default physical schema for the same data server.

Category:
Other

Cause:

Action:

ODI-10119
A different Context is already set as the default Context.

Category:
Other

Cause:

Action:

ODI-10120
Context code will be changed from <{0}> to <{1}>.

Category:
Other

Cause:
The import will make a change to an existing context code.

Action:
Determine whether the change to context code is desired or not.

ODI-10121
Logical schema name will be changed from <{0}> to <{1}>.

Category:
Other

Cause:
The import will make a change to an existing logical schema name.

Action:
Determine whether the change to logical schema name is desired or not.

ODI-10122
Logical agent name will be changed from <{0}> to <{1}>.

Category:
Other

Cause:
The import will make a change to an existing logical agent name.

Action:
Determine whether the change to logical agent name is desired or not.

ODI-10123
{0} with {1} <{2}> and {3} <{4}> does not exist.

Category:
Other

Cause:
A referenced object does not exist.

Action:
Either import the missing object or change to reference a different object.

ODI-10124
Smart import of file {0} cannot be run due to unfixed critical issues.

Category:
Other

Cause:
Critical issues exist for objects in the Smart Import.

Action:
A fix must be provided for all critical issues before the Smart Import can be run.

ODI-10125
Smart Export file name cannot be null.

Category:
Other

Cause:
Smart Export file name not specified for Smart Export.

Action:
Specify a Smart Export file via Smart Export.

ODI-10126
File {0} already exists.

Category:
Other

Cause:
The file already exists.

Action:
Specify another file name.

ODI-10127
Column position {0} is being used by another object <{1}>.

Category:
Other

Cause:
The position value is already in use.

Action:
Specify a unique position value.

ODI-10128
Multiple primary keys found. Only one primary key can be defined per datastore.

Category:
Other

Cause:
Multiple primary keys defined.

Action:
Delete or match primary keys so that only one is defined.

ODI-10129
Object with id {0} and type {1} is not a smart exportable object.

Category:
Other

Cause:
Smart Export does not support the type of object specified.

Action:
Do not export this object.

ODI-10130
Smart Import Response file {0} is not valid for Smart Export file {1}.

Category:
Other

Cause:
Smart Import Response file was not generated for the Smart Export file being imported.

Action:
Specify a Smart Import response file that belongs to the Smart Export file being imported.

ODI-10131
Entity of type {0} cannot be merged.

Category:
Programmatic

Cause:
Wrong entity type.

Action:
Check entity type.

ODI-10132
Entity of type {0} cannot be removed.

Category:
Programmatic

Cause:
Wrong entity type.

Action:
Check entity type.

ODI-10133
Cannot create a transaction against the extended persistent context [{0}].

Category:
Programmatic

Cause:
Another persistence context is already bound to the current thread.

Action:
Unbound persistence context from current thread.

ODI-10134
You do not have READ permission on at least one object from the collection/list.

Category:
Security

Cause:
Insufficient level of permissions.

Action:
Check your permissions

ODI-10135
Max value ({1}) reached for sequence {0} and reset is not allowed.

Category:
Other

Cause:
Reset is not allowed.

Action:
Check configuration of sequence behaviour.

ODI-10136
Illegal transaction state: transaction synchronization is active but entity manager is not synchronized within the transaction.

Category:
Programmatic

Cause:
Entity manager is not synchronized within the transaction.

Action:
Synchronize entity manager and try again.

ODI-10137
Your program needs to set authentication first.

Category:
Security

Cause:
There is no authentication set.

Action:
Set authentication via odiInstance.getSecurityManager().setGlobalAuthentication(.) or odiInstance.getSecurityManager().setCurrentThreadAuthentication(.), see the SecurityManager API for more detail.

ODI-10138
Unable to create DwgConnectConnection to {0} repository.

Category:
Other

Cause:
Exception during connection.

Action:
Check repository configuration.

ODI-10139
{0} must not be null or empty.

Category:
Configuration

Cause:
Parameter is null or empty.

Action:
Check parameter name.

ODI-10140
{0} must be greater or equal 0.

Category:
Configuration

Cause:
Parameter is negative.

Action:
Check parameter value.

ODI-10141
Unable to create datasource provider from class [{0}].

Category:
Configuration

Cause:
Exception during creation.

Action:
Check configuration.

ODI-10142
Active transaction is required to use the method {0} on the TransactionalOdiEntityManager.

Category:
Programmatic

Cause:
Transaction is not active.

Action:
Check transaction state.

ODI-10143
Error while accessing the {0} repository.

Category:
Network

Cause:
Network problems.

Action:
Check the network connection and the database status.

ODI-10144
OdiInstance is closed.

Category:
Other

Cause:
OdiInstance is closed.

Action:
Check OdiInstance status.

ODI-10145
Limited persistence support.

Category:
Other

Cause:
Limited persistence support.

Action:
Check OdiInstance configuration.

ODI-10146
Cannot create JDBC DataSource for this type of DataServer.

Category:
Programmatic

Cause:
Invalid connection provider.

Action:
Check connection provider.

ODI-10147
Repository type mismatches.

Category:
Configuration

Cause:
Wrong repository type.

Action:
Check repository type.

ODI-10148
Repository is in error install/upgrade state and needs to be repaired. Connection has been disabled.

Category:
Configuration

Cause:
Repository install/upgrade did not complete successfully.

Action:
Check install/upgrade log files and/or ODI user documentation for information on reparation process.

ODI-10149
Local Repository table is empty.

Category:
Configuration

Cause:
Local Repository table is empty.

Action:
Check repository configuration.

ODI-10150
Work repository with ID {0} is not bound to master: Definition in master ID:{0}, Name:{1}, Timestamp:{2} Definition in work ID:{3}, Name:{4}, Timestamp:{5}.

Category:
Configuration

Cause:
Work repository with ID is not bound to master repository.

Action:
Check work and master repositories configuration.

ODI-10151
Unable to get ID for entity {0}.

Category:
Security

Cause:
Wrong entity ID.

Action:
Check entity properties.

ODI-10152
I_OBJECTS for entity class {0} is not found.

Category:
Programmatic

Cause:
Entity type is not mapped to I_OBJECTS.

Action:
Check entity class.

ODI-10153
{0} is denied.

Category:
Security

Cause:
Insufficient level of permissions.

Action:
Check permissions.

ODI-10154
{0} is denied for {1}.

Category:
Security

Cause:
Insufficient level of permissions.

Action:
Check permissions.

ODI-10155
You do not have {0} permission on at least one object from the collection/list.

Category:
Security

Cause:
Insufficient level of permissions.

Action:
Check permissions.

ODI-10156
Impossible to connect to JPS MBean Server.

Category:
Configuration

Cause:
Exception during connection.

Action:
Check configuration.

ODI-10157
{0}: must call preWebLogic() before postWebLogic().

Category:
Programmatic

Cause:
Wrong API usage.

Action:
Call preWebLogic() before postWebLogic().

ODI-10158
The credential with map name {0} and key {1} already exists.

Category:
Programmatic

Cause:
Wrong credential.

Action:
Check credential configuration.

ODI-10159
The user {0} has not required CONNECT profile.

Category:
Security

Cause:
The user has not required profile.

Action:
Grant the user CONNECT profile first.

ODI-10160
Unable to load user.

Category:
Other

Cause:
Exception during user loading.

Action:
Check repository connection.

ODI-10161
Trying to create authentication with Subject parameter which should be applicable when OPSS authentication is used, but ODI shows it is using ODI internal authentication.

Category:
Programmatic

Cause:
ODI internal authentication is used instead of OPSS authentication.

Action:
Check authentication type.

ODI-10162
This OPSS user "{0}" is not registered to Oracle Data Integrator.

Category:
Configuration

Cause:
The user is not registered to ODI.

Action:
Check user name.

ODI-10163
This OPSS user "{0}" has different GUID than the one found in Oracle Data Integrator repository.

Category:
Security

Cause:
OPSS user differs from ODI user in GUID.

Action:
Check user GUID.

ODI-10164
Only supervisor user can invoke this API.

Category:
Security

Cause:
Insufficient level of permissions.

Action:
Check user role.

ODI-10165
The RunAsUser {0} is not a valid user from external user identity store.

Category:
Security

Cause:
User is not valid.

Action:
Check user.

ODI-10166
The RunAsUser: {0} has different GUID in ODI repository and external user identity store.

Category:
Security

Cause:
User from external user identity store differs from ODI user in GUID.

Action:
Check user.

ODI-10167
Authentication is missing.

Category:
Security

Cause:
Authentication is missing.

Action:
Check authentication configuration.

ODI-10168
There is already an Authentication bound to this thread.

Category:
Programmatic

Cause:
There is already an Authentication bound to this thread.

Action:
Check authentication configuration.

ODI-10169
Trying to set authentication object which is not created by this security manager.

Category:
Programmatic

Cause:
Authentication object is not created by this security manager.

Action:
Check authentication configuration.

ODI-10170
There is currently no Authentication bound to this thread.

Category:
Security

Cause:
There is currently no Authentication bound to this thread.

Action:
Check authentication configuration.

ODI-10171
There is already an Authentication bound as global Authentication.

Category:
Programmatic

Cause:
There is already an Authentication bound as global Authentication.

Action:
Check authentication configuration.

ODI-10172
There is currently no global Authentication bound to this SecurityManager.

Category:
Security

Cause:
There is currently no global Authentication bound to this SecurityManager.

Action:
Check authentication configuration.

ODI-10173
You are not authorized to change the password for external user "{0}".

Category:
Security

Cause:
Insufficient level of permissions.

Action:
Check permissions.

ODI-10174
You are not authorized to change the password for user "{0}".

Category:
Security

Cause:
Insufficient level of permissions.

Action:
Check permissions.

ODI-10175
You are not authorized to change the password for external user.

Category:
Security

Cause:
Insufficient level of permissions.

Action:
Check permissions.

ODI-10176
Authentication is needed to change password.

Category:
Security

Cause:
Authentication is missed.

Action:
Authenticate first.

ODI-10177
ODI was not able to load the jdbc driver class "{0}" provided on {1}.

Category:
Other

Cause:
Wrong jdbc driver class.

Action:
Check that the driver class name is correct and that this driver is available to ODI classloader.

ODI-10178
The jdbc URL "{1}" was not accepted by the jdbc driver class "{0}" provided on {2}.

Category:
Other

Cause:
Insufficient jdbc URL.

Action:
Check that the jdbc URL and the driver class name are matching.

ODI-10179
Client requires a repository with version {0} but the repository version found is {1}.

Category:
Other

Cause:
Insufficient repository version.

Action:
Check repository configuration.

ODI-10180
ODI was not able to load the jdbc driver class {0} specified in ODI topology for work repository {1}.

Category:
Other

Cause:
Wrong jdbc driver class.

Action:
Check that the driver class name is correct and that this driver is available to ODI classloader. If the driver class name is incorrect please connect to ODI topology to fix it.

ODI-10181
Uncategorized configuration exception.

Category:
Configuration

Cause:
An unexpected error occurred.

Action:
Check exception cause for details.

ODI-10182
Uncategorized exception during repository access.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Check exception cause for details.

ODI-10183
{0} is an invalid finder class.

Category:
Programmatic

Cause:
Wrong finder class.

Action:
Check finder class.

ODI-10184
Could not get ESS {0}.

Category:
Session

Cause:
Exception during session retrieving.

Action:
Check configuration and try again.

ODI-10185
Operation is not granted.

Category:
Security

Cause:
Current level of permission is not sufficient.

Action:
Check your permissions.

ODI-10186
User {0} is inactive.

Category:
Security

Cause:
There is no GUID defined for this User in ODI repository

Action:
Check user GUID.

ODI-10187
The authentication API is used in wrong way.

Category:
Programmatic

Cause:
The authentication API is used in wrong way.

Action:
Check usage of API.

ODI-10188
Error while login from OPSS.

Category:
Other

Cause:
Exception was thrown during login process.

Action:
Make sure OPSS is configured correctly for this installation.

ODI-10189
The password violates the following rule: "Password policy {0}". Select another password.

Category:
Security

Cause:
Weak password

Action:
Check password policy and correct password.

ODI-10190
The user {0} has its account expired.

Category:
Security

Cause:
Account expired

Action:
Request supervisor for account unlocking.

ODI-10191
Unable to create datasource provider.

Category:
Configuration

Cause:
Exception during creation.

Action:
Check configuration.

ODI-10192
Unable to retrieve user GUID.

Category:
Other

Cause:
Exception during GUID retrieving.

Action:
Check repository connection.

ODI-10193
Unexpected null value in port.

Category:
Programmatic

Cause:
JPS port value is null.

Action:
Check JPS configuration.

ODI-10194
Uncategorized security exception.

Category:
Programmatic

Cause:
An unexpected error occurred.

Action:
Check exception cause for details.

ODI-10195
CsfAccessor is only available for CsfPasswordStorageConfiguration

Category:
Programmatic

Cause:
Password storage configuration is internal.

Action:
Check storage configuration.

ODI-10196
Error while accessing the repository.

Category:
Network

Cause:
Network problems.

Action:
Check the network connection and the database status.

ODI-10197
Instance is not connected to a work repository

Category:
Programmatic

Cause:
Work datasource is null.

Action:
Check work datasource.

ODI-10198
Context with code '{0}' was not found.

Category:
Programmatic

Cause:
Context was not found.

Action:
Check context code.

ODI-10199
Incorrect ODI username or password.

Category:
Security

Cause:
Incorrect ODI username or password.

Action:
Check username and password.

ODI-10200
Work repository {0} was not found.

Category:
Programmatic

Cause:
Wrong repository name or repository is not defined.

Action:
Check repository name.

ODI-10201
The user {0} has its password expired.

Category:
Security

Cause:
Account expired

Action:
Request supervisor for changing password.

ODI-10202
Supervisor privilege is required to setup repository.

Category:
Security

Cause:
Insufficient level of permissions.

Action:
User supervisor account for this operation.

ODI-10203
Transaction state is illegal.

Category:
Programmatic

Cause:
Transaction state is illegal.

Action:
Check transaction state.

ODI-10204
Inappropriate usage of a ODI transaction API.

Category:
Programmatic

Cause:
Inappropriate usage of a ODI transaction API.

Action:
Check ODI transaction API.

ODI-10205
Unexpected rollback.

Category:
Programmatic

Cause:
Attempt to commit a transaction resulted in an unexpected rollback.

Action:
Check transaction.

ODI-10206
Transaction cannot be created.

Category:
Programmatic

Cause:
Exception was thrown during transaction creation.

Action:
Check transaction.

ODI-10207
Uncategorized exception during transaction system usage.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Check exception cause for details.

ODI-10208
Error when changing password for user {0}.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Check exception cause for details.

ODI-10209
Cannot access a closed IOdiEntityManager.

Category:
Programmatic

Cause:
IOdiEntityManager has been closed.

Action:
Check IOdiEntityManager state.

ODI-10210
File {0} does not contain any objects to be imported by Smart Import.

Category:
Other

Cause:
Smart Export file specified for Smart Import is empty.

Action:
Specify a Smart Export file with objects for importing via Smart Import.

ODI-10211
Unsupported Java Character Set: {0}

Category:
Other

Cause:
Unsupported Java Character Set.

Action:
Check Java charset.

ODI-10212
Parent object {0}: "{1}" already has child {2}: "{3}". Technical details: {2} : "{3}" (with global id: {7} and internal id: {8}) violates alternate key constraint {4} {5} for values {6}

Category:
Other

Cause:
Object violated alternate key constraint.

Action:
Check object properties and constraint's values.

ODI-10213
Fixed format file field {0} (starts at {1} ends at {2}) has a file position that overlaps with the file position of field {3} (starts at {4} ends at {5}).

Category:
Other

Cause:
Two fields from a fixed format file have overlapping file positions.

Action:
Modify the file positions or remove a field if the overlapping file positions are not correct.

ODI-10214
Fixed format file fields {0} (starts at {1} ends at {2}) and {3} (starts at {4} ends at {5}) have unused file positions between them.

Category:
Other

Cause:
Two fields from a fixed format file have unused file positions between them.

Action:
Modify the file positions if having unused file positions is not correct.

ODI-10215
It is forbidden to import a log into a repository using any other import mode except "Synonym Mode Insert".

Category:
Other

Cause:
Import mode is not "Synonym Mode Insert".

Action:
Correct import mode.

ODI-10216
Upgrade key cannot be null when importing objects from before ODI 12C.

Category:
Other

Cause:
Upgrade key is not set for import that must upgrade objects to have global ids.

Action:
Specify the upgrade key to be used.

ODI-10217
Permission check failed for instance object {0}.

Category:
Other

Cause:
Permission check failed for instance object.

Action:
Need to grant initial permission for creator on object.

ODI-10218
Invalid WAS_HOME ("{0}") set or WebSphere library jar ({1}) not found under WAS_HOME/plugins.

Category:
Other

Cause:
Wrong WAS_HOME set (or) WebSphere libraries (com.ibm.ws.admin.core.jar, com.ibm.ws.admin.services.jar, com.ibm.ws.runtime.jar) are moved

Action:
Check that the environment-variable WAS_HOME is set properly to point to WebSphere Application Server root. Also, ensure the libraries exist under WAS_HOME/plugins.

ODI-10219
ODI Library for WebSphere access ({0}) not found.

Category:
Other

Cause:
Library could be moved / deleted

Action:
Check that the specified library present

ODI-10220
ODI was unable to find the technology "{0}".

Category:
Other

Cause:
Missing technology.

Action:
Check that this technology is defined in the repository. .

ODI-10221
It is taken {0} second to synchronize Snp_Ent_Principal table content.

Category:
Other

Cause:

Action:

ODI-10222
The compatible Mapping/ReusableMapping {0} can only be modified by 11g SDK.

Category:
Other

Cause:
An attempt was made to modify compatible Mapping using 12c SDK.

Action:
Modify compatible Mapping using 11g Interface SDK.

ODI-10223
A non-legacy compatible import source cannot be imported into a legacy compatible repository.

Category:
Other

Cause:
An attempt was made to import a non-legacy compatible import source into a legacy compatible repository.

Action:
Import a legacy compatible import source or make repository not legacy compatible.

ODI-10224
You are not authorized to create new user.

Category:
Security

Cause:
Only SUPERVISOR could create users.

Action:
Check permissions.

ODI-10225
Invalid wallet password: A valid password must have a minimum length of eight characters and contain alphabetic characters combined with numbers or special characters.

Category:
Security

Cause:
Invalid wallet password.

Action:
Please choose a valid wallet password accordingly.

ODI-10226
Wallet already exists.

Category:
Security

Cause:
Try to create a wallet which already exists.

Action:
Please stop creating a wallet. Instead use the existing one.

ODI-10227
Wallet new password is same as old password.

Category:
Security

Cause:
You provide a new wallet password which is the same as the old one.

Action:
Please choose different wallet password than the old one.

ODI-10228
Repository with id "{0}" or with name "{1}" has been already used in your master repository.

Category:
Configuration

Cause:
Master repository has already work repository with the same name or id.

Action:
Check your master repository and work repository.

ODI-10229
Repository with id "{0}" has been already used in your master repository.

Category:
Configuration

Cause:
Master repository has already work repository with the same id.

Action:
Check your master repository and work repository.

ODI-10230
Repository with name "{0}" has been already used in your master repository.

Category:
Configuration

Cause:
Master repository has already work repository with the same name.

Action:
Check your master repository and work repository.

ODI-10231
Interface {0} cannot be imported because source temporary interface / mapping {1} is not found.

Category:
Other

Cause:
An attempt was made to import an interface with a source temporary interface / mapping that cannot be found in the import source or target repository.

Action:
Import the missing source temporary interface / mapping.

ODI-10232
The password violates the following rule: "New password must be different from old one". Select another password.

Category:
Security

Cause:
Weak password

Action:
Check password policy and correct password.

ODI-10234
Object cannot be imported since it contains non XML files

Category:
Other

Cause:
ZipFolder to be imported should not contain non XML files

Action:
Check ZipFolder to be imported

ODI-10235
No Importable files found

Category:
Other

Cause:
None of XML files imported from ZipFolder

Action:
Check XML files to be imported from Zip Folder

ODI-10236
Object must be replaced with an object of same KM type

Category:
Other

Cause:
KM of different type to the existing KM was selected for import replace.

Action:
Import Replace KM with existing KM type

ODI-10237
Object not replaced

Category:
Other

Cause:
A KM was selected for the Import Replace with a different type to the current KM.

Action:
Select a KM of the same type for import replace.

ODI-10238
Object must be replaced with an object of same type

Category:
Other

Cause:
Different ODI object is used to Import Replace KM

Action:
Import Replace KM with Same type

ODI-10239
Importing file "{0}"...

Category:
Files

Cause:

Action:

ODI-10240
Updating dataservers...

Category:
Topology

Cause:

Action:

ODI-10241
Removing Error Tables for Physical Schema with id "{0}"

Category:
Topology

Cause:

Action:

ODI-10242
Removing Error Table "{0}"

Category:
Topology

Cause:

Action:

ODI-10243
Cannot import an export file with parents using regular import and INSERT_UPATE mode. Use smart import instead.

Category:
Other

Cause:
An attempt was made to import an export file created with parent objects using regular import and INSERT_UPATE mode. This would cause all other objects under the parent objects and not in the import file to be deleted.

Action:
Use smart import to import an export file created with parent objects when INSERT_UPDATE functionality is needed.

ODI-10244
Cannot import {0} {1} (with global id: {2} and internal id: {3}) because referenced {4} with global id {5} does not exist.

Category:
Other

Cause:
The referenced object for a foreign key cannot be found in order to set the reference and a missing reference cannot be created.

Action:
Import the missing referenced object before importing the referencing object.

ODI-10245
Cannot import {0} {1} (with global id: {2} and internal id: {3}) belonging to {4} {5} (with global id: {6} and internal id: {7}) because its referenced object is not found in the target repository.

Category:
Other

Cause:
The object was imported in a SYNONYM UPDATE mode and the referenced object was not found in the repository.

Action:
Change the import mode to INSERT_UPDATE or import the file twice first in INSERT MODE and then in UPDATE mode.

ODI-10246
No Exportable objects found in the repository.

Category:
Other

Cause:
No objects are present in the repository for export

Action:
Create repository objects

ODI-10247
Specified project {0} does not exist in the repository.

Category:
Other

Cause:
The repository did not contain the specified project.

Action:
Choose another project or create the project with the specified name.

ODI-10248
{0} : Not an ODI special driver.

Category:
Other

Cause:
Invalid Special driver.

Action:
Check that this technology is part of the special driver list.

ODI-13000
Invalid Directory Path specified - {0}

Category:
Other

Cause:
Invalid directory path. Either the path does not exist or is not a directory

Action:
Provide valid directory path

ODI-13001
Error Fetching Objects From File

Category:
Other

Cause:
Error Fetching Objects From File

Action:
Check The File

ODI-13002
Error Fetching Objects From Version Control System

Category:
Other

Cause:
Error Fetching Objects From Version Control System

Action:
Check The Repository

ODI-13003
Error Fetching Objects From Folder

Category:
Other

Cause:
Error Fetching Objects From Folder

Action:
Check Either the path does not exist or is not a directory

ODI-13005
Error Listing Branches From VCS

Category:
Other

Cause:
Error Listing Branches From VCS

Action:
Check The Repository

ODI-13006
Error Exporting Objects To Memory

Category:
Other

Cause:
Error Exporting Objects To Memory

Action:
Check The Object List

ODI-13007
Error Creating Temp Dir

Category:
Other

Cause:
Error Creating Temp Dir

Action:
Check The Path / Permission

ODI-13008
Error Listing NonEmpty Branches From Version Control System

Category:
Other

Cause:
Error Listing NonEmpty Branches From Version Control System

Action:
Check The Repository

ODI-13009
Error Listing NonEmpty Tags From Version Control System

Category:
Other

Cause:
Error Listing NonEmpty Tags From Version Control System

Action:
Check The Repository

ODI-13010
Error querying merge objects

Category:
Other

Cause:
Error Fetching SnpObjects

Action:
Check The Repository

ODI-13011
An in progress merge already exists. Only one in progress merge is allowed at a time.

Category:
Other

Cause:
A different in progress merge already exists

Action:
Complete the merge that is in progress before attempting to start another merge.

ODI-13012
In progress merge objects still exist for the merge. All merge objects must be complete before merge status can be set to complete.

Category:
Other

Cause:
In progress merge objects still exist for the merge

Action:
Complete the merge for all in progress merge objects in order to complete the merge.

ODI-13013
This operation is supported only when the object is deleted in SOURCE.

Category:
Other

Cause:
This operation is supported only when the object is deleted in SOURCE.

Action:
Perform delete object operation when object is deleted in SOURCE.

ODI-13014
An object ({0} {1}) identified as new for a merge cannot be added due to:

Category:
Other

Cause:
A different object already exists with the same name which causes the adding of the object to fail.

Action:
Delete or rename the conflicting object in the merge target, or rename the object in the merge source.

ODI-13015
This operation is supported only when the object is added in SOURCE.

Category:
Other

Cause:
This operation is supported only when the object is added in SOURCE.

Action:
Perform delete object operation when object is added in SOURCE.

ODI-13700
Unable to set the role OWB_USER for this user.

Category:
Other

Cause:
An attempt was made to set the role OWB_USER for the connected user.

Action:
Check that the role exists and the connected user is an OWB user.

ODI-13701
Unable to set the workspace {0} for this user.

Category:
Other

Cause:
An attempt was made to select the OWB workspace for the connected user.

Action:
Check that the workspace exists and the connected user has got privilege to access it.

ODI-13702
Unexpected error when connecting to OWB workspace {0}.

Category:
Other

Cause:
An unexpected error occurred when connecting to workspace.

Action:
Verify that the Owb repository is up and running.

ODI-13703
Unexpected error when locating object {0} in OWB workspace {1}.

Category:
Other

Cause:
An unexpected error occurred when locating an object in a workspace

Action:
Verify that the Owb repository is up and running and the object exists.

ODI-13704
Could not locate the physical schema associated with OWB workspace {0} in context {1}.

Category:
Other

Cause:
An error occurred when finding the schema related to an OWB workspace in a context.

Action:
Verify that the OWB workspace is related to a physical schema in the context.

ODI-13800
Cannot locate the monitor configuration file: {0} using JVM argument: {1}={2} or the environment variable: {3}={4}.

Category:
Configuration

Cause:

Action:

ODI-13801
Cannot locate the monitor configuration file at: {0}.

Category:
Configuration

Cause:

Action:

ODI-13802
Cannot access the monitor configuration file: {0}.

Category:
Configuration

Cause:

Action:

ODI-13803
The contents of the monitor configuration file: {0} are invalid.

Category:
Configuration

Cause:

Action:

ODI-13804
The runtime performance monitoring has been turned off due to invalid monitor configuration.

Category:
Configuration

Cause:

Action:

ODI-13805
An error occured while updating the monitor status for the Agent:{0}, Master repository external id:{1}

Category:
Other

Cause:

Action:

ODI-13806
An error occurred while starting the pre execution monitor for Agent={0}, Master repository external id={1}, Scenario={2}

Category:
Other

Cause:

Action:

ODI-13807
An error occurred while stopping the pre execution monitor for Agent={0}, Master repository external id={1}, Scenario={2}

Category:
Other

Cause:

Action:

ODI-13808
An error occurred while starting the request processing monitor for Agent={0}, Master repository external id={1}

Category:
Other

Cause:

Action:

ODI-13809
An error occurred while stopping the request processing monitor for Agent={0}, Master repository external id={1}

Category:
Other

Cause:

Action:

ODI-13810
An error occurred while starting the execution monitor for Agent={0}, Master repository external id={1}, Scenario={2}

Category:
Other

Cause:

Action:

ODI-13811
An error occurred while stopping the execution monitor for Agent={0}, Master repository external id={1}, Scenario={2}

Category:
Other

Cause:

Action:

ODI-13812
An error occurred while starting the post execution monitor for Agent={0}, Master repository external id={1}, Scenario={2}

Category:
Other

Cause:

Action:

ODI-13813
An error occurred while stopping the post execution monitor for Agent={0}, Master repository external id={1}, Scenario={2}

Category:
Other

Cause:

Action:

ODI-13814
An error occurred while starting the Scenario execution monitor for Agent={0}, Master repository external id={1}, Scenario={2}

Category:
Other

Cause:

Action:

ODI-13815
An error occurred while stopping the Scenario execution monitor for Agent={0}, Master repository external id={1}, Scenario={2}

Category:
Other

Cause:

Action:

ODI-13816
An error occurred while starting the Step execution monitor for Agent={0}, Scenario={1}, Step={2}

Category:
Other

Cause:

Action:

ODI-13817
An error occurred while stopping the Step execution monitor for Agent={0}, Scenario={1}, Step={2}

Category:
Other

Cause:

Action:

ODI-13818
An unexpected error occurred while starting the entity monitor for entity={0}, agent={1}, master repository external id={2}, session id={3}

Category:
Other

Cause:

Action:

ODI-13819
An unexpected error occurred while updating the entity monitor for entity={0}, agent={1}, master repository external id={2}, session id={3}

Category:
Other

Cause:

Action:

ODI-13820
An unexpected error occurred while starting the entity monitor for entity={0}, agent={1}, master repository external id={2}, session id={3}

Category:
Other

Cause:

Action:

ODI-13821
An error occurred while registering the Agent Discovery Mbean, mbeanName={0}

Category:
Other

Cause:

Action:

ODI-13822
An error occurred while de-registering the Agent Discovery Mbean, mbeanName={0}

Category:
Other

Cause:

Action:

ODI-13823
Could not find the Server MBean for server {0} on platform {1}.

Category:
Other

Cause:

Action:

ODI-14000
Importing Object

Category:
Other

Cause:

Action:

ODI-14001
Importing Profile

Category:
Other

Cause:

Action:

ODI-14002
Importing User

Category:
Other

Cause:

Action:

ODI-14003
Importing InstObj

Category:
Other

Cause:

Action:

ODI-14004
Importing Local Repository

Category:
Other

Cause:

Action:

ODI-14005
Importing Techno

Category:
Other

Cause:

Action:

ODI-14006
Importing Data Types

Category:
Other

Cause:

Action:

ODI-14007
Importing Data Types Conversions

Category:
Other

Cause:

Action:

ODI-14008
Importing Language

Category:
Other

Cause:

Action:

ODI-14009
Importing Open Tools

Category:
Other

Cause:

Action:

ODI-14010
Importing Pwd Policies

Category:
Other

Cause:

Action:

ODI-14011
Importing Pwd Rule

Category:
Other

Cause:

Action:

ODI-14012
Importing Connection

Category:
Other

Cause:

Action:

ODI-14013
Importing Agent

Category:
Other

Cause:

Action:

ODI-14014
Importing LBAgent

Category:
Other

Cause:

Action:

ODI-14015
Importing Logical Agent

Category:
Other

Cause:

Action:

ODI-14016
Importing Context

Category:
Other

Cause:

Action:

ODI-14017
Importing Pschema

Category:
Other

Cause:

Action:

ODI-14018
Importing Lschema

Category:
Other

Cause:

Action:

ODI-14019
Importing Entity

Category:
Other

Cause:

Action:

ODI-14020
Importing Link

Category:
Other

Cause:

Action:

ODI-14021
Importing Field

Category:
Other

Cause:

Action:

ODI-14022
Importing FieldLook Up

Category:
Other

Cause:

Action:

ODI-14023
Importing Look Up

Category:
Other

Cause:

Action:

ODI-14024
Importing Look Up Value

Category:
Other

Cause:

Action:

ODI-14025
Importing Action

Category:
Other

Cause:

Action:

ODI-14026
Importing Action Group

Category:
Other

Cause:

Action:

ODI-14027
Importing Version

Category:
Other

Cause:

Action:

ODI-14028
Importing Solutions

Category:
Other

Cause:

Action:

ODI-14029
Cleaning connections

Category:
Other

Cause:

Action:

ODI-14030
Importing:

Category:
Other{0}

Cause:

Action:

ODI-14031
Importing Session

Category:
Other

Cause:

Action:

ODI-14032
Importing Global Sequences

Category:
Other

Cause:

Action:

ODI-14033
Importing Global Variables

Category:
Other

Cause:

Action:

ODI-14034
Importing Global User Functions

Category:
Other

Cause:

Action:

ODI-14035
Importing Global Group of States

Category:
Other

Cause:

Action:

ODI-14036
Importing Model Folders

Category:
Other

Cause:

Action:

ODI-14037
Importing Models

Category:
Other

Cause:

Action:

ODI-14038
Importing Scenario folders

Category:
Other

Cause:

Action:

ODI-14039
Importing Projects

Category:
Other

Cause:

Action:

ODI-14040
Importing Scenario

Category:
Other

Cause:

Action:

ODI-14041
Importing Folders

Category:
Other

Cause:

Action:

ODI-14042
Importing Packages

Category:
Other

Cause:

Action:

ODI-14043
Importing Interfaces

Category:
Other

Cause:

Action:

ODI-14044
Importing Procedures

Category:
Other

Cause:

Action:

ODI-14045
Importing Knowledge Modules

Category:
Other

Cause:

Action:

ODI-14046
ODI Master Repository Upgrade: Upgrading Repository Structure...

Category:
Upgrade

Cause:

Action:

ODI-14047
ODI Master Repository Upgrade: Upgrading Repository Data...

Category:
Upgrade

Cause:

Action:

ODI-14048
ODI Master Repository Upgrade: Done.

Category:
Upgrade

Cause:

Action:

ODI-14049
Master repository creation is successful.

Category:
Other

Cause:

Action:

ODI-14050
ODI Work Repository Attach: Attaching Repository...

Category:
Other

Cause:

Action:

ODI-14051
ODI Work Repository Attach: Done.

Category:
Other

Cause:

Action:

ODI-14052
ODI Work Repository Upgrade: Upgrading Repository Structure...

Category:
Upgrade

Cause:

Action:

ODI-14053
ODI Work Repository Upgrade: Upgrading Repository Data...

Category:
Upgrade

Cause:

Action:

ODI-14054
ODI Work Repository Upgrade: Done.

Category:
Upgrade

Cause:

Action:

ODI-14055
Work repository creation is successful.

Category:
Other

Cause:

Action:

ODI-14056
Importing SubModels

Category:
Other

Cause:

Action:

ODI-14057
Importing Tables

Category:
Other

Cause:

Action:

ODI-14058
End importing {1}. Import time (milliseconds): {0}.

Category:
Other

Cause:

Action:

ODI-14059
End importing {1}. Import time (hh:mm:ss): {0}.

Category:
Other

Cause:

Action:

ODI-14060
End importing {0}.

Category:
Other

Cause:

Action:

ODI-14061
Master repository already up to date nothing to do.

Category:
Other

Cause:

Action:

ODI-14062
Upgrading master repository from {0} to {1}

Category:
Other

Cause:

Action:

ODI-14063
Applying DDL from file {0}

Category:
Other

Cause:

Action:

ODI-14064
Error while applying DDL from file {0}

Category:
Other

Cause:
Exception during execution of session.

Action:
Check session.

ODI-14065
Work repository already up to date. Nothing to do.

Category:
Upgrade

Cause:

Action:

ODI-14066
upgrade error while executing {0} params = {1}

Category:
Upgrade

Cause:
Wrong parameters at Sql query.

Action:
Check parameters.

ODI-14067
Exporting {0}

Category:
Other

Cause:

Action:

ODI-14068
End exporting {1}. Export time (milliseconds): {0}

Category:
Other

Cause:

Action:

ODI-14069
End exporting {1}. Export time (hh:mm:ss): {0}.

Category:
Other

Cause:

Action:

ODI-14070
Import failed. The parent object was not found in the repository.

Category:
Other

Cause:
The object was imported in a SYNONYM mode and the parent object was not found in the repository.

Action:
Change the import mode or restore the parent object in the repository

ODI-14071
Getting Dependencies

Category:
Other

Cause:

Action:

ODI-14072
End getting dependencies. Time (milliseconds): {0}

Category:
Other

Cause:

Action:

ODI-14073
End getting dependencies. Time (hh:mm:ss): {0}.

Category:
Other

Cause:

Action:

ODI-14074
Parent folder already has the release tag set.

Category:
Other

Cause:
Setting the release tag when the parent already has the release tag set.

Action:
Set the release tag in parent.

ODI-14075
Seed data for property missing.

Category:
Other

Cause:
Seed data for property {0} is missing.

Action:
Contact Oracle Support Services

ODI-14077
Importing Mappings/Reusable Mappings

Category:
Other

Cause:

Action:

ODI-14078
Importing Mapping Component Types

Category:
Other

Cause:

Action:

ODI-14079
Importing Enterprise Scheduler

Category:
Other

Cause:

Action:

ODI-14080
Importing Enterprise Principals

Category:
Other

Cause:

Action:

ODI-14081
User Function syntax is not unique.

Category:
Other

Cause:
Work repository already has User Function with the same syntax.

Action:
Check your user function syntax.

ODI-14085
Object cannot be Imported since it contains non XML file

Category:
Other

Cause:
Folder to be imported should not contain non XML files

Action:
Check Folder to be imported

ODI-14086
Begin importing: {0}

Category:
Other

Cause:

Action:

ODI-14087
Total Time For Import (before Upgrade of Interfaces) : {0} (milliseconds)

Category:
Other

Cause:

Action:

ODI-14088
Total Time For Import (before Upgrade of Interfaces) : {0} (hh:mm:ss)

Category:
Other

Cause:

Action:

ODI-14089
Total Time for Import:{0} (milliseconds)

Category:
Other

Cause:

Action:

ODI-14090
Total Time for Import: {0} (hh:mm:ss)

Category:
Other

Cause:

Action:

ODI-14091
Work repository is already attached to another master repository.

Category:
Other

Cause:
Attempt to attach already attached work repository was made while work repository can be attached to only one master repository at the moment.

Action:
Work repository should be first detached from the master repository it is attached to at the moment.

ODI-14092
Loading Master Repository Info

Category:
Other

Cause:

Action:

ODI-14093
Cannot Connect To Master Repository

Category:
Other

Cause:
Cannot Connect To Master Repository

Action:
Check your connection settings or database

ODI-14094
Master Repository Is In Invalid State.

Category:
Other

Cause:

Action:

ODI-14095
Master Repository Already Up To Date.

Category:
Other

Cause:

Action:

ODI-14096
Error While Upgrading Master Repository {0}

Category:
Other

Cause:
Exception caught while upgrading Master Repository

Action:
Please check the Logs.

ODI-14097
Importing Technology Seed Data

Category:
Other

Cause:

Action:

ODI-14098
Error While Importing Technology Seed Data {0}

Category:
Other

Cause:
Exception caught while importing technology Seed Data

Action:
Please check the logs

ODI-14099
Scanning Export Files

Category:
Other

Cause:

Action:

ODI-14100
Loading Technology

Category:
Other

Cause:

Action:

ODI-14101
Checking for Pre 4.3.3.2 Version

Category:
Other

Cause:

Action:

ODI-14102
Upgrading To Master Repository Till 4.3.3.2 Version

Category:
Other

Cause:

Action:

ODI-14103
Upgrading Master Repository Post 4.3.3.2 Version

Category:
Other

Cause:

Action:

ODI-14104
Reimporting Metadata

Category:
Other

Cause:

Action:

ODI-14105
Reimporting Security Seed Data

Category:
Other

Cause:

Action:

ODI-14106
Getting Work Repositories

Category:
Other

Cause:

Action:

ODI-14107
Found {0} Work Repositories to Upgrade

Category:
Other

Cause:

Action:

ODI-14108
Upgrading {0} Work Repository

Category:
Other

Cause:

Action:

ODI-14109
Cannot Connect To Work Repository

Category:
Other

Cause:
Cannot Connect To Work Repository {0}

Action:
Check your connection settings or database

ODI-14110
Work Repository {0} Is In Invalid State.

Category:
Other

Cause:

Action:

ODI-14111
Work Repository Already Up To Date.

Category:
Other

Cause:

Action:

ODI-14112
Converting All Interface to Mapping

Category:
Other

Cause:

Action:

ODI-14113
Work repository is already attached to the master repository.

Category:
Other

Cause:
Attempt to attach already attached work repository was made.

Action:
Please do not attach the work repository again to the master repository.

ODI-14114
Incorrect wallet password.

Category:
Security

Cause:
Provided wallet password is incorrect.

Action:
Please enter correct wallet password.

ODI-14115
Wallet file {0} is not found at specified location.

Category:
SECURITY

Cause:
Wallet file is not present.

Action:
Please check if wallet file is present at specified location.

ODI-14116
No registry database provided

Category:
Other

Cause:
Registry database not provided.

Action:
Please provide registry database.

ODI-14117
No repository database in URL: {0}

Category:
Other

Cause:
Repository database missing from the jdbc url.

Action:
Please provide repository database in the jdbc url.

ODI-14118
Not a valid jdbc mysql url: {0}

Category:
Other

Cause:
Invalid JDBC mysql url

Action:
Please provide a valid jdbc url.

ODI-14119
The selected database was released after this version of Oracle Fusion Middleware. For the most recent list of certified databases, refer to the Supported System Configurations information on the Oracle Technology Network.

Category:
Other

Cause:
Database version is not supported

Action:
Refer to the certification matrix for supported DB versions.

ODI-14120
The database you are connecting is not a supported version. refer to the certification matrix for supported DB versions.

Category:
Other

Cause:
Database version is not supported

Action:
Refer to the certification matrix for supported DB versions.

ODI-14121
The selected Oracle Database 11g Release 2 instance is not certified with this version of Oracle Fusion Middleware. Oracle Fusion Middleware 12c requires Oracle Database 11g Release 2 (11.2.0.3) or higher. For the latest list of certified databases, refer to the Supported System Configurations information on the Oracle Technology Network.

Category:
Other

Cause:
Database version is not supported

Action:
Refer to the certification matrix for supported DB versions.

ODI-14122
The database you are connecting is not a supported version. Enter Database with version equal to or higher than 10.5.3.0. Refer to the certification matrix for supported DB versions

Category:
Other

Cause:
Database version is not supported

Action:
Refer to the certification matrix for supported DB versions.

ODI-14123
DB Init Param Prerequisite failure for innodb_file_format. Its value should be 'Barracuda'.

Category:
Other

Cause:
INNODB_FILE_FORMAT value is not 'Barracuda'.

Action:
Refer to the certification matrix for supported DB init parameters.

ODI-14124
The selected MySQL instance is not certified with this version of Oracle Fusion Middleware. Oracle Fusion Middleware 12c requires MySQL 5.5.14 or higher. For a list of certified databases, refer to the Supported System Configurations information on the Oracle Technology Network.

Category:
Other

Cause:
Database version is not supported

Action:
Refer to the certification matrix for supported DB versions.

ODI-14125
DB Init Param Prerequisite failure for innodb_file_per_table. Its value should be 'ON'

Category:
Other

Cause:
INNODB_FILE_PER_TABLE value is not 'ON'

Action:
Refer to the certification matrix for supported DB init parameters.

ODI-14126
DB Init Param Prerequisite failure for innodb_large_prefix. Its value should be 'ON'.

Category:
Other

Cause:
INNODB_LARGE_PREFIX value is not 'ON'

Action:
Refer to the certification matrix for supported DB init parameters.

ODI-14127
DB Init Param Prerequisite failure for log_bin_trust_function_creators. Its value should be 'ON'.

Category:
Other

Cause:
log_bin_trust_function_creators value is not 'ON'

Action:
Refer to the certification matrix for supported DB init parameters.

ODI-14128
The selected Oracle database is a multitenant container database (CDB). Connecting to a multitenant container database (CDB) is not supported. Instead, connect to a valid pluggble database (PDB).

Category:
Other

Cause:
Database version is not supported

Action:
Refer to the certification matrix for supported DB versions.

ODI-14129
The selected Oracle Database 12c instance is not certified with this version of Oracle Fusion Middleware. Oracle Fusion Middleware 12c requires Oracle Database 12c (12.1.0.1) or higher. For a list of certified databases, refer to the Supported System Configurations information on the Oracle Technology Network

Category:
Other

Cause:
Database version is not supported

Action:
Refer to the certification matrix for supported DB versions.

ODI-14130
The selected Oracle Database 11g Release 1 or Oracle Database 10g instance is not certified with this version of Oracle Fusion Middleware. Oracle Fusion Middleware 12c requires Oracle Database 10g (10.2.0.4) or higher or Oracle Database 11g Release 1 (11.1.0.7) or higher. For the latest list of certified databases, refer to the Supported System Configurations information on the Oracle Technology Network.

Category:
Other

Cause:
Database version is not supported

Action:
Refer to the certification matrix for supported DB versions.

ODI-14131
The database you are connecting is not a supported version. Enter Database with version equal to or higher than 2008 R2. Refer to the certification matrix for supported DB versions.

Category:
Other

Cause:
Database version is not supported

Action:
Refer to the certification matrix for supported DB versions.

ODI-14132
The selected IBM DB2 instance is not certified with this version of Oracle Fusion Middleware. Oracle Fusion Middleware 12c requires IBM DB2 9.7 or higher in 9 series and IBM DB2 10.1 FP2 or higher in 10 series. For a list of certified databases, refer to the Supported System Configurations information on the Oracle Technology Network.

Category:
Other

Cause:
Database version is not supported

Action:
Refer to the certification matrix for supported DB versions.

ODI-14133
User should have sysdba or dba privilages.

Category:
Other

Cause:
User does not have sysdba or dba privilages

Action:
Grant user sysdba or dba privilages.

ODI-14134
The selected Oracle database is not configured to use the AL32UTF8 character set. Oracle strongly recommends using the AL32UTF8 character set for databases that support Oracle Fusion Middleware.

Category:
Other

Cause:
The database you are connecting is with non-AL32UTF8 character set

Action:
Use AL32UTF8 as the database character set.

ODI-14135
Table schema_version_registry$ already exists. Please use correct database.

Category:
Other

Cause:
Table schema_version_registry$ already exists.

Action:
Use correct database.

ODI-14136
Database does not match the requirement.

Category:
Other

Cause:
Database validation failed

Action:
Refer to the certification matrix for supported DB versions.

ODI-14137
Error occurred while validating database {0}.

Category:
Other

Cause:
Database validation failed

Action:
Refer to the certification matrix for supported DB versions.

ODI-14138
Could not perform validation of the database.Please check the database user privileges.

Category:
Other

Cause:
Database validation failed

Action:
Check if database user has sufficient privileges or required table/view/file exist .

ODI-14139
Encryption Standard is not set in Master Repository.

Category:
Security

Cause:
Master Repository configured with invalid or no Encryption Standard.

Action:
Set the Encryption Standard to be used in the Master Repository, with valid value for algorithm ('AES') and key-length ('128' / '256').

ODI-14140
Master key data is not set in Master Repository

Category:
Security

Cause:
Master Repository does not have the master key data.

Action:
Set the Master key data to be used in the Master Repository.

ODI-14141
The provided key is not matching the key-specification. Key must : be of length 8-100, contain at least one alphabet (lower/uppercase), contain at least one numeric-digit (or) a special-character from: [@ # $ % + / =].

Category:
Security

Cause:
The provided key is not matching the key-specification.

Action:
Provide key that matches the key-specification

ODI-14142
The Security Policy currently in force, does not allow the use of AES-256.

Category:
Security

Cause:
The Security Policy in force does not allow using AES-256 Encryption Standard.

Action:
To use AES-256, please replace the security policy files in JRE_HOME/lib/security, with Unlimited Strength Policy Files available at Java SE downloads at http://www.oracle.com/technetwork/java. Refer Java SE documentation for more information.

ODI-14143
Encryption Standard persisted in master repository is not AES-128 or AES-256.

Category:
Security

Cause:
The Encryption Standard configured in the repository is not supported.

Action:
Edit the master repository configuration to set the Encryption Standard as AES-128 or AES-256.

ODI-14144
An Error occurred while parsing the ODI Tool Command

Category:
Security

Cause:
An error occurred while parsing the ODI Tool Command text.

Action:
Refer to stack trace for more details.

ODI-14145
An Error occurred while setting parameter {0} in ODI Tool Command.

Category:
Security

Cause:
Unable to set parameter in ODI Tool Command.

Action:
Refer to stack trace for more details.

ODI-14146
Incorrect Export Key

Category:
Security

Cause:
The Export Key provided is incorrect for the import source

Action:
Provide a valid Export Key that was used during Export of object

ODI-14147
An error occurred while migrating cipher text in object {0} - "{1}" (with Internal ID: {2} and Global ID: {3})

Category:
Security

Cause:
Invalid Cipher content or Invalid Export Key

Action:
If exporting, check if the cipher data present in the object is correct. If importing, check if Export Key is correct.

ODI-14148
An Error occurred while creating Cipher for migration.

Category:
Security

Cause:
An error occurred while creating ODI Cipher.

Action:
Refer to stack trace for more details

ODI-14149
Invalid Encoder/Decoder for Cipher Text Migration.

Category:
Security

Cause:
The ODI Encoder/Decoder is invalid.

Action:
Create valid Encoder/Decoder for Cipher Text Migration.

ODI-14150
An Error occurred while migrating password cipher text

Category:
Security

Cause:
An error occurred while migrating the password cipher text

Action:
Refer to stack trace for more details

ODI-14151
An error occurred while retrieving parameters from ODI Tool Command.

Category:
Security

Cause:
Invalid ODI Tool Command.

Action:
Check ODI Tool Command text.

ODI-14152
Package name is not unique.

Category:
Other

Cause:
Duplicate package name. Package with the same name already exists in this folder.

Action:
Choose another package name.

ODI-14153
Procedure name is not unique.

Category:
Other

Cause:
Duplicate procedure name. Procedure with the same name already exists in this folder.

Action:
Choose another procedure name.

ODI-14154
Context name is not unique.

Category:
Other

Cause:
Context with the same name already exists.

Action:
Check your context name.

ODI-14155
Context code is not unique.

Category:
Other

Cause:
Context with the same code already exists.

Action:
Check your context code.

ODI-14156
KM name is not unique.

Category:
Other

Cause:
Duplicate KM name. KM with the same name already exists.

Action:
Choose another KM name.

ODI-14157
Procedure option name is not unique.

Category:
Other

Cause:
Duplicate procedure option name. Procedure option with the same name already exists.

Action:
Choose another procedure option name.

ODI-14158
A Supervisor user can be updated only by another Supervisor user.

Category:
Security

Cause:
The logged-in user is not a Supervisor user, but trying to update another Supervisor user.

Action:
Login as a user with right privileges.

ODI-14159
An error occurred while validating the Export Key.

Category:
Security

Cause:
An error occurred while validating the export key

Action:
Please check the Logs

ODI-14160
Skipping Data migration on IP Text {0} . Failed with Exception : {1} . Please fix manually.

Category:
Security

Cause:
An error occurred while migrating the password cipher text

Action:
Refer to Error Message for more details

ODI-14161
Duplicate name objects are found in the repository. Please check the upgrade log file.

Category:
Other

Cause:
Some objects with same names are under same parents

Action:
Check the log file for the duplicate name objects. Remove them before upgrade

ODI-14162
User cannot login ODI with blank password. Please contact SUPERVISOR to reset the password.

Category:
Security

Cause:
User cannot login ODI with blank password. Please contact SUPERVISOR to reset the password.

Action:
Please contact SUPERVISOR to reset the password.

ODI-14163
User cannot create master repository through import with blank supervisor password.

Category:
Security

Cause:
User cannot create master repository through import with blank supervisor password.

Action:
Please provide valid supervisor password to the API while create master repository thorugh import.

ODI-14164
Work repository name must not be null or empty

Category:
Other

Cause:
Work repository name is null or empty.

Action:
Check Work repository name.

ODI-14165
The repository is currently locked for sync operation and cannot be modified

Category:
Repository

Cause:
User cannot make any changes as repository is locked for sync.

Action:
Please try after some time.

ODI-14166
Importing Project Marker Groups

Category:
Other

Cause:

Action:

ODI-14167
Importing Project Sequences

Category:
Other

Cause:

Action:

ODI-14168
Importing Project Variables

Category:
Other

Cause:

Action:

ODI-14169
Importing Project User Functions

Category:
Other

Cause:

Action:

ODI-14170
Importing Project Knowledge Modules

Category:
Other

Cause:

Action:

ODI-14171
Importing Project Reusable Mappings

Category:
Other

Cause:

Action:

ODI-14172
Importing Project Mappings

Category:
Other

Cause:

Action:

ODI-14173
The repository is for {0} so you cannot connect to this repository from {1}.

Category:
Security

Cause:
Repository is not valid for the invoking application.

Action:
Connect to this repository use the proper application.

ODI-14174
You are using Oracle Golden Gate Studio which only supports internal authentication mode. But the repositgory is in external authentication mode which cannot be used for Oracle Golden Gate Studio.

Category:
Security

Cause:
The repository is in external authentication mode and it is not valid for Oracle Golden Gate Studio since Oracel Golden Gate Studio only supports internal authentication mode. One possibility could be that this repository is for Oracle Data Integrator.

Action:
Connect to a different repository.

ODI-14175
Cannot delete this user since it is the last supervisor user.

Category:
Security

Cause:
You are trying to delete the last supervisor user which cannot deleted.

Action:
Create another user and make it supervisor user and then you can delete this supervisor user.

ODI-14176
Password cannot be empty for accessing the MBean Server, which is used for External Password Storage.

Category:
Security

Cause:
Password is empty for the accessing the MBean Server.

Action:
Provide MBean server password.

ODI-14177
The external user: {0} does not exist in ODI repository and also has no ODI role granted. The GUID of the user : {1}

Category:
Security

Cause:
The specified external user does not exists in ODI repository and has no ODI role granted.

Action:
Add the external user in ODI repository or grant required ODI roles to the user.

ODI-14178
Schema name and Catalog name is not unique for the dataserver {0}

Category:
Other

Cause:
Duplicate physical schema. Physical Schema with the same schema name and catalog name already exists for this dataserver.

Action:
Choose another schema name and/or catalog name.

ODI-14179
For security reasons, you cannot use odiRef.getJDBCConnection("WORKREP"), since your Work Repository and Master Repository use the same database schema. Please contact your Oracle Data Integrator Administrator to grant you <Create JDBC Connection> permission on Master Repository object from Oracle Data Integrator Studio Security Explorer and try again. Please note that the <Create JDBC Connection> permission is located under Master Repository object in the Objects section from Security Explorer. You can give the permission to a user, say User1, by 1) drag and drop it to the user User1 2) then mark the newly granted permission as Generic Privilege: the newly granted permission <Create JDBC Connection> will be under the tree node User1/Objects/Master Repository, open the editor of the granted permission and select the check box named <Generic Privilege>.

Category:
Other

Cause:
The Work Repository and Master Repository use same database schema and you do not have the required permission granted.

Action:
Please contact your Oracle Data Integrator Administrator to grant you <Create JDBC Connection> permission on Master Repository object from Oracle Data Integrator Studio Security Explorer and try again. Or you also can re-create your Master and Work repositories in different database schema. Please note that the <Create JDBC Connection> permission is located under Master Repository object in the Objects section from Security Explorer. You can give the permission to a user, say User1, by 1) drag and drop it to the user User1 2) then mark the newly granted permission as Generic Privilege: the newly granted permission <Create JDBC Connection> will be under the tree node User1/Objects/Master Repository, open the editor of the permission and select the check box named <Generic Privilege>.

ODI-14180
{0}. Data migration is skipped for URL : {1}

Category:
Upgrade

Cause:
The format of the URL is incorrect or the URL contains invalid properties.

Action:

ODI-14181
Upgrading Converson Datatype Global Ids

Category:
Other

Cause:

Action:

ODI-14182
Error While Upgrading Conversion Datatype Global Ids {0}

Category:
Other

Cause:
Exception caught while upgrading conversion datatype (SnpConvDt) Global Ids

Action:
Please check the logs

ODI-14183
The Schema Version Registry Table already exists at {0}.

Category:
Other

Cause:
Schema Version Registry Table already exists.

Action:
Please use correct database.

ODI-14184
Unable to load required classes from {0} Data Server Classpath

Category:
Other

Cause:
Required Classes cannot be loaded from the Classpath specified in the Data Server

Action:
Please specify correct classpath in Data Server

ODI-14185
Unable to load Client: {0}

Category:
Other

Cause:
Client Classes cannot be loaded from the Classpath

Action:
Please check the logs

ODI-14186
Importing Dimension Model

Category:
Other

Cause:

Action:

ODI-14187
Importing Dimension

Category:
Other

Cause:

Action:

ODI-14188
Importing Cube

Category:
Other

Cause:

Action:

ODI-14189
Unable to connect to the Server via broker(s): {0}. Check Connection Settings.

Category:
Other

Cause:
Unable to connect to the Server.

Action:
Please check the connection settings

ODI-14190
Importing OGG Projects

Category:
Other

Cause:

Action:

ODI-14191
Importing OGG Solutions

Category:
Other

Cause:

Action:

ODI-14192
Importing OGG Folders

Category:
Other

Cause:

Action:

ODI-14193
Importing OGG Mappings

Category:
Other

Cause:

Action:

ODI-14194
Objects with null global id's are present in repository. Please check the upgrade log file.

Category:
Other

Cause:
Some objects with NULL global id's are present in repository

Action:
Manually Assign GUID to the objects which got NULL value before upgrade.

ODI-14195
Duplicate name objects and objects with null GUID are found in the repository. Please check the upgrade log file.

Category:
Other

Cause:
Some objects with same names are under same parents and some objects with NULL GOLBAL_ID value

Action:
Remove duplicate named objects and manually assign unique GUID to the objects which got NULL value before upgrade.

ODI-14196
BICS Table Operation File Input Stream cannot be obtained.

Category:
Other

Cause:
BICS Table Operation File Path is not provided by user or invalid, hence input stream cannot be obtained.

Action:
Set valid BICS Table Operation File Pat.

ODI-14197
BICS Dataset Operation File Input Stream cannot be obtained.

Category:
Other

Cause:
BICS Dataset Operation File Path is not provided by user or invalid, hence input stream cannot be obtained.

Action:
Set valid BICS Dataset Operation File Pat.

ODI-14198
BICS Target Type is invalid.

Category:
Other

Cause:
Invalid BICS Target Type is provided by user(it should be table or dataset).

Action:
Set valid BICS Target Type.

ODI-14199
Cannot change BICS Operation property: {0}. Value has already been specified and it is immutable object.

Category:
Other

Cause:
User is trying to set value to immutable member which already has value in it.

Action:
Please do not set value of immutable object.

ODI-14200
You can only grant or retrieve enterprise principal member or ODI internal user member on role object. But this is an user object.

Category:
Security

Cause:
The application invoked some API on an user object, instead the API should be invoked on a role object.

Action:
This is an internal error. Please contact Oracle Support Services with details.

ODI-14201
This method is only applicable to Oracle Golden Gate Studio. But your repository is ODI.

Category:
Security

Cause:
The application invoked some API which is only applicable to Oracle Golden Gate Studio. But your application is configured as ODI.

Action:
This is an internal error. Please contact Oracle Support Services with details.

ODI-14202
Importing KM Template

Category:
Other

Cause:

Action:

ODI-14203
You do not have <Credential Access> permission on data server {0}. Please ask your Oracle Data Integrator Administrator or Security Administrator to grant you the permission. Please note: 1) The administrator first needs to grant you the non-generic <Credential Access> permission by drag-and-drop it to a user from Studio Security Explorer , this non-generic permission is located under Data Server object in the Objects section from Security Explorer; 2) Then the administrator needs to grant you the data server instance permission e.g. drag-and-drop the data server {1} on a user and check method <Credential Access> and save.

Category:
Security

Cause:
You do not have <Credential Access> permission on a data server

Action:
Please ask your Oracle Data Integrator Administrator or Security Administrator to grant you the permission. Please note: 1) The administrator first needs to grant you the non-generic <Credential Access> permission by drag-and-drop it to a user from Studio Security Explorer, this non-generic permission is located under Data Server object in the Objects section from Security Explorer; 2) Then the administrator needs to grant you the data server instance permission e.g. drag-and-drop the data server on a user and check method <Credential Access> and save.

ODI-14204
Method must be redefined in derived class: {0} for Foreign Key: {1}

Category:
Other

Cause:
Method must be redefined in derived class.

Action:
Call redefined method.

ODI-14205
{0} name is not unique.

Category:
Other

Cause:
Another object with the same name exists.

Action:
Choose another name.

ODI-14206
Import failed due to unable to delete unneeded objects in target repository.

Category:
Other

Cause:
Deletion of unneeded target objects failed due to sql constraint violation.

Action:
Contact Oracle Support Services.

ODI-14207
Oracle supplied KM must be imported using DUPLICATION mode cannot be imported using import replace

Category:
Other

Cause:
Oracle supplied KM must be imported by Duplication Mode

Action:
Import Oracle Supplied KM by Duplication mode.

ODI-14208
ImportReplaceKMFromXML API is used to import a KM File

Category:
Other

Cause:
XML File do not contain Procedure object

Action:
XML file must contain an OdiProcedure.

ODI-14209
Argument {0} cannot be null to export Delta artifacts

Category:
Other

Cause:
Argument cannot be null

Action:
Argument cannot be null.

ODI-14210
HDFS directory does not exist : {0}

Category:
Other

Cause:
HDFS directory does not exist.

Action:
HDFS directory must exist.

ODI-14211
Local directory does not exist : {0}

Category:
Other

Cause:
Local directory does not exist.

Action:
Local directory must exist.

ODI-14212
Argument : {0} is mandatory

Category:
Other

Cause:
Argument cannot be null.

Action:
Argument cannot be null.

ODI-14213
Input parameter {0} is not valid. It is either null/empty or invalid.

Category:
Other

Cause:
Input Parameter is invalid.

Action:
Provide valid input.

ODI-14214
Failed to connect to Object Storage.

Category:
Other

Cause:
Contact Oracle Support Services.

Action:
Verify connection parameters.

ODI-14215
Failed to perform {0} on Object Storage.

Category:
Other

Cause:
Contact Oracle Support Services.

Action:
Contact Oracle Support Services.

ODI-14216
Physical schema {0} is not configured for required field {1}.

Category:
Other

Cause:
Invalid Physical schema value specified.

Action:
Update Physical schema with proper values required for Object Storage.

ODI-14217
Input parameter {0} is not matching for specified users {1}.

Category:
Other

Cause:
Invalid input parameters specified.

Action:
Verify input parameters.

ODI-14218
{0} should be specified when {1} is specified.

Category:
Other

Cause:
Invalid input parameters specified.

Action:
Verify input parameters.

ODI-14219
Wallet file {0} is not accessible.

Category:
Security

Cause:
Wallet file is not accesible.

Action:
Please check Wallet file permission.

ODI-14220
{0} directory {1} configured for field {2} for Physical schema {3} does not exists.

Category:
Other

Cause:
Invalid input parameters specified.

Action:
Verify input parameters.

ODI-14221
Physical schema is not configured for required field {0}.

Category:
Other

Cause:
Empty Physical schema value specified.

Action:
Update Physical schema with proper values required for Object Storage.

ODI-14222
Wallet file {0} does not contain connection information.

Category:
Security

Cause:
Wallet file doesnot have required information.

Action:
Please add connection details to Wallet file.

ODI-14223
Wallet file {0} does not contain credentials for given connection information.

Category:
Security

Cause:
Wallet file doesnot have required credential information.

Action:
Please add credential information to Wallet file for given connection information.

ODI-14224
Service URL {0} has wrong Protocol

Category:
Other

Cause:
Service URL has wrong Protocol

Action:
Please use correct URL to connect to Oracle Storage Cloud Service

ODI-14225
Incorrect UserName, Password or Identity Domain is provided.

Category:
Other

Cause:
Invalid credentials provided to connect to Oracle Storage Cloud Service

Action:
Please provide correct credentials to connect to Oracle Storage Cloud Service

ODI-14226
Invalid Service URL {0} is provided.

Category:
Other

Cause:
Invalid Service URL to connect to Oracle Storage Cloud Service

Action:
Please use correct Service URL to connect to Oracle Storage Cloud Service

ODI-14227
{0} cannot be NULL. Please provide Valid {0} to connect Oracle Storage Cloud Service

Category:
Other

Cause:
{0} Cannot be NULL

Action:
Please use correct {0} to connect to Oracle Storage Cloud Service

ODI-14229
Failed to connect to Oracle Storage Cloud Service

Category:
Other

Cause:
Failed to Download. File Count not matching with Object count in Container to download

Action:
Failed to Download. Please Check valid File Count matching Object count in Container to download

ODI-14230
Failed to {0}.Please use appropriate Storage Container Type to {0} STANDARD or ARCHIVE File Type

Category:
Other

Cause:
Failed to {0}. Invalid Container Storage Type for STANDARD | ARCHIVE type

Action:
Failed to {0}. Please Correct Storage Container Type accordingly to {0} STANDARD or ARCHIVE File type

ODI-14231
Physical schema {0} is not configured for required field {1}.

Category:
Other

Cause:
Invalid Physical schema value specified.

Action:
Update Physical schema with proper values required for Storage CS.

ODI-14232
{0} directory {1} configured for field {2} for Physical schema {3} does not exists.

Category:
Other

Cause:
Invalid input parameters specified.

Action:
Verify input parameters.

ODI-14233
{0} container {1} configured for field {2} for physical schema {3} does not exist.

Category:
Other

Cause:
Invalid input parameters specified.

Action:
Verify input parameters.

ODI-14234
{0} bucket {1} configured for field {2} for physical schema {3} does not exist.

Category:
Other

Cause:
Invalid input parameters specified.

Action:
Verify input parameters.

ODI-14235
Credential zip {0} does not contain required tnsnames.ora.

Category:
Security

Cause:
Credential zip doesnot have required tnsnames.ora.

Action:
Please add required file tnsnames.ora in credential zip.

ODI-14236
Tnsnames file in {0} does not contain connection information.

Category:
Security

Cause:
TnsNames.ora is empty.

Action:
Please add connection information in tnsnames.ora in credential zip.

ODI-14237
Credential zip {0} can not be found.

Category:
Security

Cause:
Credential zip is not found.

Action:
Please check the location. Retry.

ODI-14238
Credential file {0} is not found at specified location {1}

Category:
SECURITY

Cause:
Credential file is not present.

Action:
Please check if credential file is present in Credential zip.

ODI-14240
Service name : {0} cannot contain '-'. Provide valid Service name.

Category:
Other

Cause:
Invalid input parameters specified.

Action:
Verify input parameters.

ODI-14241
Invalid Service Name. Service : {0} does not exist.

Category:
Other

Cause:
Check Service Name.

Action:
Invalid Service name

ODI-14242
Failed to get list of containers.

Category:
Other

Cause:
Contact Oracle Support Services.

Action:
Contact Oracle Support Services

ODI-14243
Failed to delete the container : {0}.

Category:
Other

Cause:
Contact Oracle Support Services.

Action:
Contact Oracle Support Services

ODI-14244
Failed to create the container : {0}.

Category:
Other

Cause:
Contact Oracle Support Services.

Action:
Contact Oracle Support Services

ODI-14245
Failed to fetch the service : {0}.

Category:
Other

Cause:
Invalid input parameters specified.

Action:
Verify input parameters.

ODI-14246
Failed to perform {0} on Storage CS.

Category:
Other

Cause:
Contact Oracle Support Services.

Action:
Contact Oracle Support Services

ODI-14247
Credential zip {0} is not accessible.

Category:
Security

Cause:
Credential zip is not accessible.

Action:
Verify permission and path accessibility.

ODI-14248
Unable to unzip Credential zip {0}

Category:
Others

Cause:
Error while trying to unzip credential zip.

Action:
Verify zip uploaded.

ODI-14249
Unable to encrypt files during Upload.

Category:
Other

Cause:
Invalid Encryption key provided.

Action:
Verify Encryption key.

ODI-14250
Invalid decrypt key provided.

Category:
Other

Cause:
Invalid Decryption key provided.

Action:
Verify Decryption key.

ODI-14251
Unable to decrypt files during Download.

Category:
Other

Cause:
Invalid Decryption key provided.

Action:
Verify Decryption key.

ODI-14252
Physical schema is not defined for the logical schema {0}.

Category:
Other

Cause:
Invalid input parameters specified.

Action:
Verify input parameters.

ODI-14253
Provided {0} logical schema {1} is not supported.

Category:
Other

Cause:
Invalid Logical schema value specified.

Action:
Update Logical schema with proper values.

ODI-14254
An error occurred while unzipping the DA file to directory {0}.

Category:
Other

Cause:
An error occurred while unzipping the DA file

Action:
Please check permission.

ODI-14255
Import file has repository version {0} newer than current repository version {1}. This import is not supported.

Category:
Other

Cause:
Import file repository version is greater than current repository version.

Action:
Use supported import file.

ODI-15000
BSF Not Present

Category:
Programmatic

Cause:
Bean Scripting Framework manager cannot be found.

Action:
Ensure that class org.apache.bsf.BSFManager is available in the classpath.

ODI-15001
No End Separator for the following text:

Category:
Programmatic

Cause:
No end delimiter found for a delimited text in the expression.

Action:
Add an end delimiter to the delimited text.

ODI-15002
The string to be transformed cannot be null.

Category:
Programmatic

Cause:
Parsing failed for an expression reference tag.

Action:
Fix the expression.

ODI-15003
Error during Code Interpretor creation

Category:
Programmatic

Cause:
Code generator internal error.

Action:
Contact Oracle support.

ODI-15005
The datatype "{0}" does not exist in technology: {1}.

Category:
Programmatic

Cause:
The datatype for a column is not supported by the technology.

Action:
Change the datatype or the technology of the execution location.

ODI-15006
The source datatype is null for the column: {0}, and the technology: {1}

Category:
Programmatic

Cause:
The datatype for a column is null for the technology.

Action:
Change the datatype or the technology of the execution location.

ODI-15007
Syntax not set for 'Create Table' for the datatype: {0} for the technology: {1}.

Category:
Programmatic

Cause:
The execution location technology does not have any "Create Table" syntax set up.

Action:
Edit the technology definition and add "Create Table" syntax.

ODI-15009
No text for the 'Writable Datatype Syntax' for the datatype: {0} in technology: {1}

Category:
Programmatic

Cause:
The datatype does not have a "Writable Datatype Syntax" property value set up for the execution location technology.

Action:
Edit the datatype in the technology to add a "Writable Datatype Syntax".

ODI-15010
No conversion for the datatype {0}, for the source technology {1} and for the target technology {2}

Category:
Programmatic

Cause:
No conversion is defined for the source technology datatype to the target technology datatype.

Action:
Edit the source or target technology datatype to add a conversion from the source to the target datatype.

ODI-15011
The variable does not exist in the database.

Category:
Programmatic

Cause:
A variable is being referenced but it does not exist in the repository.

Action:
Create the variable in the repository.

ODI-15012
Sequence does not exist in database

Category:
Programmatic

Cause:
A sequence is referenced but does not exist in the repository.

Action:
Create the sequence in the repository.

ODI-15013
The table {0} has fatal errors.

Category:
Programmatic

Cause:
The table cannot be processed.

Action:
Check the table for inconsistencies.

ODI-15014
The referenced text does not exist in the database.

Category:
Programmatic

Cause:
The text reference in the expression does not exist in the repository.

Action:
Repository corruption has occurred, contact Oracle support.

ODI-15015
Too much recursion in this text resolution.

Category:
Programmatic

Cause:
The expression text references other text recursively too many times.

Action:
Review the expression and try to simplify.

ODI-15016
Commands Undefined.

Category:
Programmatic

Cause:
KM is missing a block of lines.

Action:
Check the KM.

ODI-15017
Table not selected (null).

Category:
Programmatic

Cause:
Target table not found.

Action:
Check interface for consistency.

ODI-15018
CKM not selected.

Category:
Programmatic

Cause:
The CKM is not selected for the object.

Action:
Select a CKM.

ODI-15019
Missing context

Category:
Programmatic

Cause:
The context object cannot be found.

Action:
Check the context selection.

ODI-15020
No JKM available

Category:
Programmatic

Cause:
JKM has not been set or is not found.

Action:
Set a valid JKM for the interface.

ODI-15021
Journalizing requires a Primary Key on the Table:

Category:
Programmatic

Cause:
Journalizing is enabled, but the target table has no primary key.

Action:
Add a primary key to the target table.

ODI-15022
No RKM Set.

Category:
Programmatic

Cause:
RKM has not been set or is not found.

Action:
Set a valid RKM for the object.

ODI-15023
Cannot perform standard reverse. Choose customized reverse and set RKM.

Category:
Programmatic

Cause:
Standard reverse engineering is not supported for this object.

Action:
Select customized reverse engineering for the object and select an RKM.

ODI-15025
The interface clause text does not exist.

Category:
Programmatic

Cause:
The interface clause refers to text that does not exist.

Action:
Check interface clauses for (join, filter, etc.) for consistency.

ODI-15026
Interface clauses are missing.

Category:
Programmatic

Cause:
The code generator cannot find the clause collection for the interface.

Action:
Check the interface for consistency.

ODI-15027
Interface source tables are missing.

Category:
Programmatic

Cause:
The code generator cannot find the source table collection for the interface.

Action:
Check the interface for consistency.

ODI-15028
Interface result collection is null.

Category:
Programmatic

Cause:
Interface generation method buildSqlCauses as been called with a null results parameter.

Action:
Ensure that a non null Map is passed for the result parameter.

ODI-15029
Interface error clause collection is missing.

Category:
Programmatic

Cause:
Interface generation method buildSqlCauses as been called with a null error clauses parameter.

Action:
Ensure that a non null collection is passed for the error clauses parameter.

ODI-15030
Interface is missing the integration work table collection.

Category:
Programmatic

Cause:
Interface generation method buildSqlCauses as been called with a null work table collection parameter.

Action:
Ensure that a non null collection is passed for the work table parameter.

ODI-15031
Technology not selected.

Category:
Programmatic

Cause:
No technology is selected for the interface target execution location.

Action:
Check the technology selection for the interface target.

ODI-15032
Unknown object in interface source table collection

Category:
Programmatic

Cause:
Interface generation method buildSqlCauses as been called with a source table collection having a non table item.

Action:
Ensure that only table type items are included in the source table collection.

ODI-15033
The expression: {0} does not have an associated column.

Category:
Programmatic

Cause:
The expression should represent a column, but no column is found for the name.

Action:
Fix the expression.

ODI-15034
A scenario with the same name and the same number already exists. Please select other values.

Category:
Programmatic

Cause:
Cannot create a duplicate scenario with the same name and version number as an existing scenario.

Action:
Give the scenario a different name or version.

ODI-15036
Scenario"s name and/or number are missing.

Category:
Programmatic

Cause:
A scenario must have a name and version, but the name or version is missing.

Action:
Set values for name and version for the scenario.

ODI-15037
The interface {0} has fatal errors.

Category:
Programmatic

Cause:
The interface has fatal errors.

Action:
Check and fix interface issues.

ODI-15038
The scenario name substitution pattern {0} is not supported. Please check the user parameter for the scenario naming convention.

Category:
Programmatic

Cause:
Invalid substitution pattern used for scenario name.

Action:
Change the substitution pattern.

ODI-15039
The interface {0} use native sequence. Native sequence are not allowed for Derived Table (sub select statement)

Category:
Programmatic

Cause:
Native sequence was used in a sub-select or derived interface.

Action:
Remove the native sequence usage.

ODI-15040
Errors detected when building SQL clauses.

Category:
Programmatic

Cause:
An error occurred when generating code for the SQL clauses.

Action:
Fix the interface clauses.

ODI-15041
An aggregation function may not be used in a join condition. Please use a separate interface for the aggregation and join the result in this interface.

Category:
Programmatic

Cause:
An aggregation function was used inside a join condition expression.

Action:
Change the join condition to remove the aggregation function.

ODI-15042
Unable to regenerate this scenario. It references an package that does not exist.

Category:
Programmatic

Cause:
The scenario must reference a package, but it doesn't.

Action:
Delete the scenario and create a new one.

ODI-15043
Unable to regenerate this scenario from a Runtime repository.

Category:
Programmatic

Cause:
The scenario must cannot be regenerated from the runtime repository.

Action:
Delete the scenario and create a new one.

ODI-15044
Invalid pScenSource type when calling SnpGeneratorSQLCIT.mainGenScenSourceScenario

Category:
Programmatic

Cause:
The scenario generator has been invoked with an invalid scenario source.

Action:
Ensure that only valid scenario source types are used to generate a scenario.

ODI-15045
Invalid value for KM type.

Category:
Programmatic

Cause:
An invalid value was specified for the KM type.

Action:
Specify a valid value.

ODI-15046
The column cache is null during code generation.

Category:
Programmatic

Cause:
The getSnpCol method has been invoked while the SnpColCache member is null;

Action:
Ensure that SnpGeneratorSQLCIT has been properly initialized before invoking getSnpCol.

ODI-15047
The getSnpCol method has been invoked with a null column ID during code generation.

Category:
Programmatic

Cause:
The getSnpCol method has been invoked with a null column ID.

Action:
Ensure that getSnpCol is only called with valid column ID values.

ODI-15050
Flow Control not possible if no key is declared in your target datastore

Category:
Programmatic

Cause:
Flow control is enabled for the interface, but the target datastore has no primary key defined.

Action:
Define a primary key for the target datastore object, and re-add the target datastore.

ODI-15051
Missing mapping instance for interface.

Category:
Programmatic

Cause:
The target column does not have any mapping.

Action:
Add a mapping expression for the target column.

ODI-15052
The interface is missing a dataset.

Category:
Programmatic

Cause:
There is no dataset for the interface source.

Action:
Check the interface for consistency.

ODI-15054
Scenario generation error: Cannot regenerate the scenario. The physical mapping design used to generated the scenario is not found.

Category:
Programmatic

Cause:
The physical mapping design used to generated the scenario is not found.

Action:
Choose to create or replace the scenario.

ODI-15055
Character "]" missing in: {0}.

Category:
Programmatic

Cause:
A bracketed tag inside a KM line is missing a closing bracket ("]") character.

Action:
Fix the KM line.

ODI-15057
Non-ordered outer join not supported for technology.

Category:
Programmatic

Cause:
Non-ordered outer join syntax disabled for technology.

Action:
Correct join.

ODI-15058
Variable scenario generation error: Logical schema is required.

Category:
Programmatic

Cause:
Variable scenario cannot be generated if logical schema is not set.

Action:
Set the logical schema.

ODI-15059
I_TXT is mandatory.

Category:
Programmatic

Cause:
A call was made to SnpTxtCachedHashMap.getInstance, but the pITxt parameter was null.

Action:
Contact Oracle support.

ODI-15060
The JKM line {0} uses an unsupported execution channel: {1}

Category:
Programmatic

Cause:
A line in the JKM uses an execution channel that is not supported.

Action:
Change the line in the JKM to use a supported channel.

ODI-15061
The JKM line {0} uses an unsupported commit type: {1}

Category:
Programmatic

Cause:
A line in the JKM uses a commit type that is not supported.

Action:
Change the line in the JKM to use a supported commit type.

ODI-15062
Invalid commit type: {0}

Category:
Programmatic

Cause:
An invalid commit type was passed to SnpServiceGenerator.convertCommitType

Action:
Contact Oracle support

ODI-15063
The alternate key {0} is not unique.

Category:
Programmatic

Cause:
An alternate key defined by the repository is found to be non-unique.

Action:
Check the data or the alternate key definitions.

ODI-15064
The primary key {0} is not unique.

Category:
Programmatic

Cause:
A primary key defined by the repository is found to be non-unique.

Action:
Check the data or primary key definitions.

ODI-15065
Join error ({0}) between the table {1} and the table {2}.

Category:
Programmatic

Cause:
A foreign key relationship is not found.

Action:
A foreign key relationship between 2 tables defined in the repository is not valid.

ODI-15066
The column {0} cannot be null.

Category:
Programmatic

Cause:
The column is marked in the repository as not nullable.

Action:
Check the data, or change the not null value.

ODI-15067
The datatype value "{0}" is incorrect.

Category:
Programmatic

Cause:
An invalid datatype has been found.

Action:
The repository table contains an invalid datatype.

ODI-15068
Unknown flexfield code {0}.

Category:
Programmatic

Cause:
An undefined flex field code is being referenced

Action:
Check the flex field references in the KM, and the flex field definitions

ODI-15069
{0} Is not valid without session context.

Category:
Programmatic

Cause:
A current session context does not exist.

Action:
Check session definition.

ODI-15070
Unable to find method object: PythonInterpreter.initialize(Properties, Properties, String[]) method

Category:
Other

Cause:
The python method used by the script is not found.

Action:
Check the KM step.

ODI-15071
Error occurred

Category:
Other

Cause:
An exception was thrown while executing a python script in the KM step.

Action:
Check the cause.

ODI-15072
There is no PK constraint

Category:
Programmatic

Cause:
There is a call to "getPK" in the KM, but no PK is found.

Action:
Check the KM and the PK definitions.

ODI-15073
There is no index

Category:
Programmatic

Cause:
There is a call to "getIndex" in the KM, but no index is found.

Action:
Check the KM and the index definitions.

ODI-15076
no dataset

Category:
Programmatic

Cause:
A KM line is calling "getDataSet", but no data set is found.

Action:
Check the KM or the DataSet definitions.

ODI-15077
No Current Model Set

Category:
Programmatic

Cause:
There is a call to "getModel" in the KM, but no model is found.

Action:
Check the KM and the model definitions.

ODI-15078
There is no Not Null column

Category:
Programmatic

Cause:
There is a call to "getNotNullCol" in the KM, but no not null column is found.

Action:
Check the KM and the not null column definitions.

ODI-15079
There is no current Pop.

Category:
Programmatic

Cause:
There is a call to "getPop" in the KM, but no interface is found.

Action:
Check the KM and the interface definitions.

ODI-15080
There is no Step

Category:
Programmatic

Cause:
There is a call to "getStep" in the KM, but no step is found.

Action:
Check the KM and the step definitions.

ODI-15081
There is no Target Table

Category:
Programmatic

Cause:
There is a call to "getTargetTable" in the KM, but no target table is found.

Action:
Check the KM and the interface target table definitions.

ODI-15083
Multiple Primary Keys have been detected for {0} .

Category:
Programmatic

Cause:
A repository table can only have one primary key defined, but multiple primary keys are defined.

Action:
Edit the table's primary key definitions and remove all but one.

ODI-15084
There is no session

Category:
Programmatic

Cause:
There is a call to "getSession" in the KM, but no session is found.

Action:
Check the KM and the session definitions.

ODI-15085
The value : "({0})" is unknown.

Category:
Programmatic

Cause:
A KM line has a templated call which contains an unknown bracketed property.

Action:
Fix the KM.

ODI-15086
There is no Temporary Index

Category:
Programmatic

Cause:
There is a call to "getTemporaryIndex" in the KM, but no temporary index is found.

Action:
Check the KM and the temporary index definitions.

ODI-15087
There is no current execution context defined.

Category:
Programmatic

Cause:
There is a call to "getContext" in the KM, but no context is found.

Action:
Check the KM and the context definitions.

ODI-15088
Not in designer mode

Category:
Programmatic

Cause:
A KM line has a call to access design information, but the interpretation location is not set to designer.

Action:
Make sure that the interpretation location is set to designer when this line is executed.

ODI-15089
asked '({0})' and available value are between 0 and ({1}).

Category:
Programmatic

Cause:
A KM line is calling "getDataSet", but the specified index is out of range.

Action:
Fix the KM or the DataSet definitions.

ODI-15090
Table "{0}" not found on model "{1}", schema "{2}"

Category:
Programmatic

Cause:
Attempt to initialize data services from a table that cannot be found

Action:
Change data services reference or make sure that table exists

ODI-15091
Impossible to connect to JPS MBean Server

Category:
Other

Cause:
Cannot connect to JPS MBean server.

Action:
Internal Error.

ODI-15092
Unable to generate data service - the column {0} does not exist in the database.

Category:
Programmatic

Cause:
A data service references a column that does not exist

Action:
Fix the data service reference or make sure that the column exists

ODI-15093
Unable to regenerate this scenario. It references a null package.

Category:
Programmatic

Cause:
The scenario must reference a package, but the package is null.

Action:
Delete the scenario and create a new one.

ODI-15094
You must give a name for the published entity for each datastore.

Category:
Other

Cause:
A web services data store does not have a name.

Action:
Give the data store a name.

ODI-15095
Invalid entity for datastore: {0}

Category:
Other

Cause:
A web services data store has an invalid entity.

Action:
Associate the data store with a valid entity.

ODI-15096
Property name must not be null.

Category:
Programmatic

Cause:
The KM line is calling "isColAttrChanged", but the property value is null.

Action:
Internal error, contact Oracle support.

ODI-15097
Unknown value {0} for property

Category:
Programmatic

Cause:
The KM line is making a templated call, but the property value is unknown.

Action:
Fix the KM.

ODI-15098
You must define a data source for the model.

Category:
Other

Cause:
The model used by a web service does not have any data source.

Action:
Define a data source for the model.

ODI-15099
You must specify a JKM for the model.

Category:
Other

Cause:
The model used by a web service does not have an associated JKM.

Action:
Define a JKM for the model.

ODI-15100
You must define a Java package for the model.

Category:
Other

Cause:
The model used by a web service does not have an associated Java package.

Action:
Define a Java package for the model.

ODI-15101
Invalid Java package format: {0}

Category:
Other

Cause:
The Java package associated with a model has an invalid package format.

Action:
Correct the package format for the model.

ODI-15102
You must specify an XML namespace for the model.

Category:
Other

Cause:

Action:

ODI-15103
Invalid namespace: {0}

Category:
Other

Cause:
A model namespace used by a web service is invalid.

Action:
Correct the namespace for the model.

ODI-15104
You must specify an SKM for the model.

Category:
Other

Cause:
A model used by a web service does not have an associated SKM.

Action:
Add an SKM to the model.

ODI-15105
You must specify which schema the model will be deployed to.

Category:
Other

Cause:
No web service deployment schema is specified for the model.

Action:
Specify a schema to which the model will be deployed.

ODI-15106
You must specify a name for the Data Service for the model.

Category:
Other

Cause:
The data service for the model does not have a name.

Action:
Set a valid name for the data service.

ODI-15107
Invalid model code: {0}. It should follow the Java identifiers naming conventions.

Category:
Other

Cause:
The web service model name does not follow the standard Java identifier naming convention.

Action:
Set a valid name for the model.

ODI-15108
Invalid model Data Service name: {0}. It should follow the Java identifiers naming conventions.

Category:
Other

Cause:
The web service model Data Service name does not follow the standard Java identifier naming convention.

Action:
Set a valid name for the model Data Service.

ODI-15109
Invalid web service name for datastore: {0}

Category:
Other

Cause:
The web service model data store has an invalid name.

Action:
Set a valid name for the model data store.

ODI-15110
SKM is empty

Category:
Other

Cause:
The web service SKM has no valid lines.

Action:
Add some lines to the SKM.

ODI-15111
Problem during deployment

Category:
Deployment

Cause:
Internal error.

Action:
Contact Oracle support.

ODI-15113
Reverse table {0} for model {1} already exists.

Category:
Other

Cause:
An attempt was made to reverse engineer a table, but it already exists in the model.

Action:
Move or rename the data store in the model, or skip reverse engineering for the table.

ODI-15116
There is not enough data in the target file to proceed with the reverse-engineering. Please make sure the file has at least one non-empty line and number of rows to skip is correct.

Category:
Other

Cause:
An attempt was made to reverse engineer a target file that is empty, or the number of skipped rows is larger than the number of rows in the file.

Action:
Set the number of skipped lines to a lower value, or add some data to the file.

ODI-15117
Not allowed (OLD and NEW are involved)

Category:
Programmatic

Cause:
The KM line is calling "getColumn", but the ADH action origin is not "NEW" or "OLD".

Action:
Change the ADH action origin.

ODI-15118
Invalid FTP URL

Category:
Network

Cause:
The URL given for a web services FTP connection is not correct.

Action:
Check the URL for the FTP connection.

ODI-15119
Column {0} has no Java datatype.

Category:
Programmatic

Cause:
During RDB model validation, no java data type was found for a column.

Action:
Check the model and ensure that a data type has been specified.

ODI-15120
Column {0} has no String datatype.

Category:
Programmatic

Cause:
During RDB model validation, no string data type was found for a column.

Action:
Check the model and ensure that a data type has been specified.

ODI-15121
Selector must be not null

Category:
Programmatic

Cause:
The ADH selector value must not be null when "getColumn" is called from the KM line.

Action:
Change the ADH selector value.

ODI-15122
Exception getPKColList

Category:
Programmatic

Cause:
An exception was found when calling "getPKColList" during KM execution.

Action:
Fix the KM or the PK definitions.

ODI-15123
There is no AK constraint

Category:
Programmatic

Cause:
There is a call to "getAK" in the KM, but no AK is found.

Action:
Check the KM and the AK definitions.

ODI-15124
Unable to regenerate the following scenario:

Category:
Programmatic

Cause:
Cannot regenerate the scenario.

Action:
Delete the scenario and create a new one.

ODI-15125
Missing DataSet.

Category:
Programmatic

Cause:
The interface is missing a dataset.

Action:
Check interface for consistency.

ODI-15126
The sub-model must be set.

Category:
Programmatic

Cause:
The sub-model is not set for the source or target.

Action:
Check the interface for consistency.

ODI-15127
There is no CK constraint

Category:
Programmatic

Cause:
There is a call to "getCK" in the KM, but no CK is found.

Action:
Check the KM and the CK definitions.

ODI-15128
There is no FK constraint

Category:
Programmatic

Cause:
There is a call to "getFK" in the KM, but no FK is found.

Action:
Check the KM and the FK definitions.

ODI-15129
Selector value must be 'OLD' or 'NEW'

Category:
Programmatic

Cause:
The ADH selector value must be 'OLD' or 'NEW' when "getColumn" is called from the KM line.

Action:
Change the ADH selector value.

ODI-15130
Unknown object in interface source table list

Category:
Programmatic

Cause:
An invalid object was found in the SrcTableList member while processing getSrcTablesList.

Action:
Ensure the SrcTableList is only populated with type SnpTable or SnpSourceTab.

ODI-15131
You must define the name of each web service to be generated for each datastore.

Category:
Other

Cause:
A web service associated with a data store has no name.

Action:
Give a name to the web service.

ODI-15132
Exception getPK

Category:
Programmatic

Cause:
An exception was found when calling "getPK" during KM execution.

Action:
Fix the KM or the PK definitions.

ODI-15135
There is no current index.

Category:
Other

Cause:
The current index can not be found for the property name.

Action:
Check the reference.

ODI-15141
Repository is not a development work repository

Category:
Programmatic

Cause:
When getting a connection used to execute the KM, it was determined that the provided connection information does not point to a development work repository

Action:
Fix the connection information

ODI-15142
[PROPERTY: {0} not found.]

Category:
Programmatic

Cause:
The bracketed property in the KM line (e.g. "[COL_NAME]") is not found.

Action:
Fix the KM line to specify a correct property name.

ODI-15143
Invalid isolation level : {0}

Category:
Programmatic

Cause:
An invalid isolation level value was passed to SnpServiceGenerator.convertIsolationLevel

Action:
Contact Oracle support

ODI-15144
KM not encrypted since it is empty.

Category:
Other

Cause:
KM was not encrypted since it is empty.

Action:
Skip encryption.

ODI-15146
Data Type can't be null

Category:
Programmatic

Cause:
null DataType passed.

Action:
Pass non null DataType.

ODI-15147
The changes on this target column will be lost since it is not saved (it has no mapping text)

Category:
Interface Issue

Cause:
Target column will not be saved.

Action:
Enter mapping text if the column requires to be saved.

ODI-15148
The target datastore is not on the Oracle Technology: this interface cannot be used with the platform compiler

Category:
Interface Issue

Cause:
Target datastore is not on Oracle.

Action:
Move target datastore to an Oracle schema.

ODI-15149
The staging area is not on the Oracle Technology: this interface cannot be used with the platform compiler

Category:
Interface Issue

Cause:
Staging Area is not on Oracle.

Action:
Move Staging Area to an Oracle schema.

ODI-15150
The source datastore is not on the Oracle Technology: this interface cannot be used with the platform compiler

Category:
Interface Issue

Cause:
Source DataStore not on Oracle.

Action:
Use only DataStores located on an Oracle technology.

ODI-15151
Non ordered outer joins cannot be used with the platform compiler

Category:
Interface Issue

Cause:
An outer join is not ordered.

Action:
Make the join ordered.

ODI-15152
Unhandled Action {0}

Category:
Programmatic

Cause:
This shouldn't happen. Programmer added an action in the enum and forgot to add it in switch.

Action:
Add action in switch.

ODI-15153
The column is already the first column and cannot be moved up

Category:
Programmatic

Cause:
Column already first and cannot be moved up.

Action:
Do not try to move first column up.

ODI-15154
The column is already the last column and cannot be moved down

Category:
Programmatic

Cause:
Column already last and cannot be moved down.

Action:
Do not try to move last column down.

ODI-15155
Cannot move a target column to a position that is 0 or negative: {0}

Category:
Programmatic

Cause:
Trying to move a column beyond the boundaries of column positions.

Action:
Use a value between 1 and the number of columns.

ODI-15156
Cannot move a target column to a position beyond the size of the column list: {0} is greater than {1}

Category:
Programmatic

Cause:
Trying to move a column beyond the boundaries of column positions.

Action:
Use a value between 1 and the number of columns.

ODI-15157
Cannot remove the only dataset of interface {0}

Category:
Programmatic

Cause:
Trying to remove the last dataset of an interface is not permitted.

Action:
Make sure there are more than one dataset in the interface before deleting it.

ODI-15159
Cannot move target columns on a non temporary DataStore.

Category:
Programmatic

Cause:
Trying to move columns on a non temporary DataStore.

Action:
Make sure that the target DataStore is temporary before attempting to move target columns.

ODI-15160
Native Sequences may not be supported by the target technology after transforming with the Platform Compiler

Category:
Programmatic

Cause:
Using Native Sequence and Platform Compiler Enabled User Param Set

Action:
Make sure that all target technologies will support native sequences

ODI-15162
The interface {0} use native sequence. Native sequence are not allowed for Derived Table (sub select statement)

Category:
Programmatic

Cause:
Using native sequence in derived sub interface

Action:
Make sure that none sub interface using native sequence

ODI-15200
Tried to retrieve an int with an {0} object

Category:
Programmatic

Cause:
Attempted to read the column from RDB as an integer, but the column type is not integer

Action:
Internal Error: contact Oracle support

ODI-15201
Tried to retrieve a short with an {0} object

Category:
Programmatic

Cause:
Attempted to read the column from RDB as a short type, but the column type is not short

Action:
Internal Error: contact Oracle support

ODI-15202
This resultset accepts only FETCHFORWARD requests

Category:
Programmatic

Cause:
Attempted to set the fetch direction to something other than FETCH_FORWARD for a RDB result set read

Action:
Internal Error: contact Oracle support

ODI-15203
This function is unsupported: the software you are using might not be compatible with this driver.

Category:
Programmatic

Cause:
A jdbc call was made that is not supported by the currently loaded jdbc driver for RDB

Action:
Internal Error: contact Oracle support

ODI-15204
The {0} call is not implemented in this result set class.

Category:
Programmatic

Cause:
A result set call was made that is not implemented by the ODI RDB result set class

Action:
Internal Error: contact Oracle support

ODI-15205
The call is not supported in this result set class.

Category:
Programmatic

Cause:
A result set call was made that is not supported by the ODI RDB result set class

Action:
Internal Error: contact Oracle support

ODI-15206
Unmanaged numeric type {0}

Category:
Programmatic

Cause:
The RDB inserter class was passed a data value of a numeric type that is not handled

Action:
Internal Error: contact Oracle support

ODI-15207
Strange: a PK has multiple lines

Category:
Programmatic

Cause:
When selecting a parent row based on a primary key, multiple rows were returned

Action:
Internal Error: contact Oracle support

ODI-15208
The PK column of the root table has an unknown type: {0}

Category:
Programmatic

Cause:
When unloading data from the RDB, the PK column of the parent table has an unknown type

Action:
Internal Error: contact Oracle support

ODI-15209
Unsupported technology (Driver: {0}, Url: {1})

Category:
Programmatic

Cause:
The jdbc driver is not supported by the ODI RDB

Action:
Internal Error: contact Oracle support

ODI-15210
Unsupported technology: HSQL cannot create FKs after the tables have been created

Category:
Programmatic

Cause:
The Hypersonic SQL engine cannot create FK after the table is already created

Action:
Internal Error: contact Oracle support

ODI-15211
Unsupported technology: HSQL cannot create PKs after the tables have been created

Category:
Programmatic

Cause:
The Hypersonic SQL engine cannot create PK after the table is already created

Action:
Internal Error: contact Oracle support

ODI-15212
Datatype NULL (0) unsupported

Category:
Programmatic

Cause:
The Hypersonic SQL engine does not support the null datatype

Action:
Internal Error: contact Oracle support

ODI-15213
JDBC Datatype '{0}' unsupported

Category:
Programmatic

Cause:
The Hypersonic SQL engine does not support the datatype

Action:
Internal Error: contact Oracle support

ODI-15214
JDBC Datatype '{0}' with length parameter unsupported

Category:
Programmatic

Cause:
The Hypersonic SQL engine does not support the datatype with length

Action:
Internal Error: contact Oracle support

ODI-15215
JDBC Datatype '{0}' with length and scale parameters unsupported

Category:
Programmatic

Cause:
The Hypersonic SQL engine does not support the datatype with scale

Action:
Internal Error: contact Oracle support

ODI-15216
JDBC Datatype '{0}' unsupported

Category:
Programmatic

Cause:
The internal MS Sql Server database does not support the datatype

Action:
Internal Error: contact Oracle support

ODI-15217
JDBC Datatype '{0}' with length parameter unsupported

Category:
Programmatic

Cause:
The internal MS SQL Server database does not support the datatype with length

Action:
Internal Error: contact Oracle support

ODI-15218
JDBC Datatype '{0}' with length and scale parameters unsupported

Category:
Programmatic

Cause:
The internal MS SQL Server database engine does not support the datatype with length and scale

Action:
Internal Error: contact Oracle support

ODI-15219
Please transform your URL into: {0};SelectMethod=cursor

Category:
Programmatic

Cause:
The internal MS SQL Server database engine does not recognize the supplied URL

Action:
Change the format of the connection URL

ODI-15220
need length param

Category:
Programmatic

Cause:
The internal Oracle database does not support the selected type without a length param

Action:
Internal Error: contact Oracle support

ODI-15221
Datatype NULL (0) unsupported

Category:
Programmatic

Cause:
The internal Oracle SQL engine does not support the null datatype

Action:
Internal Error: contact Oracle support

ODI-15222
JDBC Datatype '{0}' unsupported

Category:
Programmatic

Cause:
The internal Oracle database does not support the datatype

Action:
Internal Error: contact Oracle support

ODI-15223
JDBC Datatype '{0}' with length parameter unsupported

Category:
Programmatic

Cause:
The internal Oracle database does not support the datatype with length

Action:
Internal Error: contact Oracle support

ODI-15224
JDBC Datatype '{0}' with length and scale parameters unsupported

Category:
Programmatic

Cause:
The internal Oracle database engine does not support the datatype with length and scale

Action:
Internal Error: contact Oracle support

ODI-15225
No key found on table {0}

Category:
Programmatic

Cause:
The internal database table does not have a key

Action:
Internal Error: contact Oracle support

ODI-15226
The root table {0} has no data

Category:
Programmatic

Cause:
The internal database table does not have any data

Action:
Internal Error: contact Oracle support

ODI-15227
Multiple keys found on table {0}

Category:
Programmatic

Cause:
The internal database table has multiple keys

Action:
Internal Error: contact Oracle support

ODI-15228
*** FATAL *** Table {0} could not be validated

Category:
Programmatic

Cause:
The internal database cannot validate the table

Action:
Internal Error: contact Oracle support

ODI-15229
*** FATAL *** Table {0} could not be found

Category:
Programmatic

Cause:
The internal database cannot find the table

Action:
Internal Error: contact Oracle support

ODI-15230
Could not convert object {0} to a {1}

Category:
Programmatic

Cause:
The internal database cannot convert the datatype of the selected column

Action:
Internal Error: contact Oracle support

ODI-15231
No '=' sign found on line {0} of bundle {1}

Category:
Programmatic

Cause:
The internal database engine encountered a syntax error when reading the property file

Action:
Fix the property file

ODI-15232
The alias {0} for table {1} is already used by another table, when reading bundle {2}

Category:
Programmatic

Cause:
The internal database found a duplicate table alias in a property file

Action:
Fix the property file

ODI-15233
Table {0} is used twice. Make sure that the table names and aliases do not conflict.

Category:
Programmatic

Cause:
The internal database found a duplicate table name in the property bundle

Action:
Fix the property file

ODI-15234
Internal RDB database table {0} not found

Category:
Programmatic

Cause:
The requested table cannot be found in the internal database

Action:
Internal Error: contact Oracle support

ODI-15235
Internal RDB database key {0} not found

Category:
Programmatic

Cause:
The requested key cannot be found in the internal database

Action:
Internal Error: contact Oracle support

ODI-15236
Unknown table {0}

Category:
Programmatic

Cause:
The requested table cannot be found in the internal database

Action:
Correct the model

ODI-15237
Duplicate table

Category:
Programmatic

Cause:
The internal database table is a duplicate table

Action:
Correct the model

ODI-15238
Could not find table although we should have created it!

Category:
Programmatic

Cause:
The newly created table cannot be found

Action:
Internal Error: contact Oracle support

ODI-15239
Only SnpsRDBDiffActionImportDifference are supported for now.

Category:
Programmatic

Cause:
When processing diff actions in a diff operation, an unsupported diff action class was found

Action:
Internal Error: contact Oracle support

ODI-15240
Unknown key {0}

Category:
Programmatic

Cause:
When processing diff actions in a diff operation, a nonexistent key was specified by the diff action

Action:
Internal Error: contact Oracle support

ODI-15241
This type of difference is not managed for now: {0}

Category:
Programmatic

Cause:
When processing diff actions in a diff operation, an unsupported diff action class was found

Action:
Internal Error: contact Oracle support

ODI-15242
Unknown difference type: {0}

Category:
Programmatic

Cause:
When processing diff actions in a diff operation, an unknown diff class was found

Action:
Internal Error: contact Oracle support

ODI-15243
Bad model number: {0}

Category:
Programmatic

Cause:
When processing diff actions in a diff operation, the 2 models that are being compared are internally numbered as model 1 and 2. A model number other than 1 or 2 was used internally in a call to getModel.

Action:
Internal Error: contact Oracle support

ODI-15244
Could not add a key because {0} is not an ID key.

Category:
Programmatic

Cause:
When building a model, the specified key class instance was not an id key

Action:
Internal Error: contact Oracle support

ODI-15245
Unknown key type: {0}

Category:
Programmatic

Cause:
When building a model, an unknown key class was found

Action:
Internal Error: contact Oracle support

ODI-15246
Key {0}.{1} is of unknown type: {2}

Category:
Programmatic

Cause:
When building a model, an unknown key class was found

Action:
Internal Error: contact Oracle support

ODI-15247
The table {0} cannot be found. It is referenced by key: {1}.

Category:
Programmatic

Cause:
When building a model, an table name is referenced by a key, but the table cannot be found

Action:
Check the model

ODI-15248
The column {0} in table {1} cannot be found. It is referenced by key: {2}.

Category:
Programmatic

Cause:
When building a model, an column name is referenced by a key, but the column cannot be found

Action:
Check the model

ODI-15249
An {0} was caught while adding a key which is not an FK. Very strange.

Category:
Programmatic

Cause:
When building a model, an column name is referenced by a key, but the column cannot be found

Action:
Check the model

ODI-15250
The key {0} referenced by table {1} cannot be found.

Category:
Programmatic

Cause:
When building a model, a key name is referenced by a table, but the key cannot be found

Action:
Check the model

ODI-15251
A duplicate key was found: {0}

Category:
Programmatic

Cause:
When dropping a model, a duplicate key was found in the model

Action:
Check the model

ODI-15252
Key already exists: {0}

Category:
Programmatic

Cause:
When updating a model, a duplicate key was found in the model

Action:
Check the model

ODI-15253
Key not found: {0}

Category:
Programmatic

Cause:
When updating a model, the key was not found

Action:
Check the model

ODI-15254
Could not find a constructor with a key name for class {0}

Category:
Programmatic

Cause:
When creating a key class instance, the constructor could not be found

Action:
Internal Error: contact Oracle support

ODI-15255
Could not instantiate an object of class {0}

Category:
Programmatic

Cause:
Could not instantiate the key class

Action:
Internal Error: contact Oracle support

ODI-15256
Could not create an object for class {0} for security reasons

Category:
Programmatic

Cause:
Could not instantiate the key class, due to a security failure

Action:
Check security settings

ODI-15257
Could create an object for class {0} because a {1} occurred saying {2}

Category:
Programmatic

Cause:
Could not instantiate the key class, due to an invocation target exception

Action:
Internal Error: contact Oracle support

ODI-15258
Column {0} not found

Category:
Programmatic

Cause:
The column could not be found

Action:
Internal Error: contact Oracle support

ODI-15259
The key class {0} is not an ID key class.

Category:
Programmatic

Cause:
The specified key class instance was not a SnpsRDBIdKey instance

Action:
Internal Error: contact Oracle support

ODI-15260
Could not add column {0}: Unsupported datatype: {1}

Category:
Programmatic

Cause:
Cannot add the column to the model because the datatype is not supported by the technology

Action:
Correct the model

ODI-15261
Unsupported action: {0}

Category:
Programmatic

Cause:
The action class is not supported by the ODI RDB

Action:
Internal Error: contact Oracle support

ODI-15262
Cannot drop column {0}. It is used in a foreign key!

Category:
Programmatic

Cause:
An attempt was made to drop a column that participates in a foreign key

Action:
Drop the key first, then the column

ODI-15263
Cannot drop column {0}. It is used in a primary key!

Category:
Programmatic

Cause:
An attempt was made to drop a column that participates in a primary key

Action:
Drop the key first, then the column

ODI-15264
Cannot modify this column. It is used in a foreign key!

Category:
Programmatic

Cause:
An attempt was made to modify a column that participates in a foreign key

Action:
Drop the key first, then modify the column

ODI-15265
Cannot modify this column. It is used in a primary key!

Category:
Programmatic

Cause:
An attempt was made to modify a column that participates in a primary key

Action:
Drop the key first, then modify the column

ODI-15268
Table not found: {0}

Category:
Programmatic

Cause:
When attempting to drop a table during an update, the table name is not found

Action:
Check the model

ODI-15270
Key type {0} is not supported here.

Category:
Programmatic

Cause:
The key type is not supported

Action:
Correct the model

ODI-15272
An error occurred while executing a RDB command: {0}

Category:
Programmatic

Cause:
When executing a command action, an exception was thrown

Action:
Check root cause

ODI-15273
{0}: action is not accepted: {1}

Category:
Programmatic

Cause:
Attempt to execute a command action, but it is not accepted

Action:
Check root cause

ODI-15274
Multiple PKs are not allowed on a table

Category:
Programmatic

Cause:
When reverse engineering a primary key, multiple primary keys were found for the table

Action:
Check the model

ODI-15275
An exception ocurred while retrieving a table primary key: {0}

Category:
Programmatic

Cause:
When reverse engineering a table, a primary key could not be retrieved

Action:
Check the model

ODI-15276
An exception occurred while retrieving the indexes of a table: {0}

Category:
Programmatic

Cause:
When reverse engineering a table, the indexes could not be retrieved

Action:
Check the model

ODI-15277
An exception ocurred while retrieving a table foreign keys: {0}

Category:
Programmatic

Cause:
When reverse engineering a table, the foreign keys could not be retrieved

Action:
Check the model

ODI-15278
An exception occurred while retrieving the check constraints of a table: {0}

Category:
Programmatic

Cause:
When reverse engineering a table, the check constraints could not be retrieved

Action:
Check the model

ODI-15279
An exception occurred while retrieving the alternate keys of a table: {0}

Category:
Programmatic

Cause:
When reverse engineering a table, the alternate keys could not be retrieved

Action:
Check the model

ODI-15280
*** FATAL *** Table {0} is duplicate as root

Category:
Programmatic

Cause:
The table is duplicated as the root when determining the root tables of the model

Action:
Check the model

ODI-15281
*** FATAL ** Table {0} is unknown

Category:
Programmatic

Cause:
The root table is unknown

Action:
Check the model

ODI-15282
Table {0} is unknown though it was reversed

Category:
Programmatic

Cause:
The table cannot be found in the ODI model, although it was reversed

Action:
Retry the reverse engineering

ODI-15283
Duplicate declaration for table {0}

Category:
Programmatic

Cause:
The model XML contains a duplicate table declaration

Action:
Fix the XML

ODI-15285
FK {0} references a table with no PK.

Category:
Programmatic

Cause:
The model XML contains a foreign key that references a table with no defined primary key

Action:
Fix the XML

ODI-15286
Unknown PK table for foreign key {0}: please check the name and order of the tables and FK.

Category:
Programmatic

Cause:
The model XML contains a foreign key that references an unknown primary key table

Action:
Fix the XML

ODI-15287
Unknown element: {0}

Category:
Programmatic

Cause:
The model XML contains an unknown element

Action:
Fix the XML

ODI-15288
An {0} error occurred with the following message: {1}

Category:
Programmatic

Cause:
An error occurred when writing the model to a file

Action:
See root cause

ODI-15290
Column {0} was not found in table {1}

Category:
Programmatic

Cause:
The column was not found when building the columns from column names

Action:
Check the model

ODI-15291
*** FATAL *** Could not rename table {0} to {1}

Category:
Programmatic

Cause:
Could not rename table

Action:
Check permissions and security settings

ODI-15292
*** FATAL *** Could not rename table {0} because it was not found in the model!

Category:
Programmatic

Cause:
Could not rename table, because the table to be renamed does not exist

Action:
Check the model

ODI-15293
Unknown FK table for foreign key {0}: please check the name and order of the tables and FK.

Category:
Programmatic

Cause:
The model XML contains a foreign key that references an unknown table

Action:
Fix the XML

ODI-15294
unknown element: {0}

Category:
Programmatic

Cause:
The model XML contains an unknown XML element

Action:
Fix the XML

ODI-15295
Unsupported datatype: {0}

Category:
Programmatic

Cause:
The datatype is unsupported when creating the column from attributes

Action:
Check the model

ODI-15300
A {0} occurred while creating the helper of class {1}. Error message: {2}

Category:
Other

Cause:
INTERNAL ERROR: A helper cannot be created.

Action:
Internal error: contact Oracle support.

ODI-15301
Choose: {0}

Category:
Other

Cause:
Choose one of the displayed options.

Action:
Choose one of the displayed options.

ODI-15302
FK is null: {0}

Category:
Other

Cause:
The FK is null, may indicate repository corruption.

Action:
Internal error: contact Oracle support.

ODI-15303
JDBC Datatype '{0}' with length '{1}' parameter unsupported

Category:
Programmatic

Cause:
MySQL database does not support the datatype with length

Action:
Internal Error: contact Oracle support

ODI-15304
JDBC Datatype '{0}' with length '{1}' and scale '{2}' parameter unsupported

Category:
Programmatic

Cause:
MySQL database does not support the datatype with scale

Action:
Internal Error: contact Oracle support

ODI-15305
JDBC Datatype '{0}' unsupported

Category:
Programmatic

Cause:
MySQL database does not support the datatype

Action:
Internal Error: contact Oracle support

ODI-15306
Column data type "{0}" not supported. Refer documentation for supported types.

Category:
Other

Cause:

Action:

ODI-15307
Metadata format of element with identifier "{0}" is incorrect. Found value "{1}"

Category:
Other

Cause:

Action:

ODI-15308
Error unloading CLOB for column "{0}"

Category:
Other

Cause:

Action:

ODI-15309
Error unloading BLOB for column "{0}"

Category:
Other

Cause:

Action:

ODI-15400
Error in generating data service

Category:
Programmatic

Cause:
Exception thrown when creating the data service used for DDL generation and reverse engineering.

Action:
Check the root cause.

ODI-15401
Unknown key {0}

Category:
Programmatic

Cause:
Unknown key encountered when processing diff class instances during DDL generation.

Action:
Check the model.

ODI-15402
Exception thrown in the DDL generation service: {0}

Category:
Programmatic

Cause:
An exception was thrown while generating DDL.

Action:
Check the root cause.

ODI-15403
The method is not supposed to sort something else than the expected actors. Attempting to sort class instances: {0}, {1}

Category:
Programmatic

Cause:
While sorting action commands, the DDL generator service encountered an unknown class instance type.

Action:
Internal Error: contact Oracle support.

ODI-15404
Scenario generation has not been implemented for this container.

Category:
Programmatic

Cause:
During DDL generation, an attempt was made to generate a scenario for an object that does not support it.

Action:
Internal Error: contact Oracle support.

ODI-15405
Scenario generation exception: {0}

Category:
Programmatic

Cause:
An exception was thrown during scenario generation.

Action:
Check root cause.

ODI-15406
Oozie workflow generation exception: {0}

Category:
Programmatic

Cause:
An exception was thrown during Oozie workflow generation.

Action:
Check root cause.

ODI-15407
Oozie workflow generation exception for Task: {0} - Transactions not supported on Oozie engine with commit mode not set. {1} command Transaction Channel: {2}.

Category:
Programmatic

Cause:
Transactions are not supported on Oozie Engine.

Action:
Please refer to documentation on Oozie Engine Execution.

ODI-15500
Column {0} is executed on the target

Category:
Programmatic

Cause:
Possible Cause

Action:
Suggested Action

ODI-15501
Cannot attach a data store to a target mapping because column {0} is not found.

Category:
Programmatic

Cause:
The specified target column was not found.

Action:
Verify that the correct column has been specified.

ODI-15502
Target mapping not found for column {0}

Category:
Programmatic

Cause:
The specified column is not mapped.

Action:
Map the specified column.

ODI-15503
Cannot set the attached datastore because the mapping is not executed on the SOURCE

Category:
Programmatic

Cause:
The mapping has been configured for execution on the target.

Action:
Configure the mapping for execution on the source.

ODI-15504
Unknown indicator type: {0}

Category:
Programmatic

Cause:
An invalid indicator type has been specified.

Action:
Specify one of the following indicator types from the IndicatorType enumeration: CHECK_NOT_NULL, INSERT, UPDATE, or UPDATE_KEY.

ODI-15505
Invalid UD number: {0}

Category:
Programmatic

Cause:
An invalid UD number has been specified.

Action:
Specify a UD number 1 to 10.

ODI-15506
The specified target column was not found: {0}

Category:
Programmatic

Cause:
The specified target column was not found when attempting to remove a column from a temporary data store.

Action:
Only remove columns which exist in the temporary target datastore.

ODI-15507
Column {0} may not be removed. It is used in other mappings, join clauses, or filter clauses

Category:
Programmatic

Cause:
The specified target column is used in other mappings, filters, or joins. This dependency prevents removal of the column.

Action:
Only remove a column after mapping, filter, or join dependencies have been removed.

ODI-15508
Column {0} may not be removed because it is referenced in interface {1}.

Category:
Programmatic

Cause:
The specified target column is referenced in a filter or join clause in another interface. This dependency prevents removal of the column.

Action:
Only remove a column after other references have been removed.

ODI-15509
The specified target column was not found: {0}

Category:
Programmatic

Cause:
The specified target column was not found.

Action:
Verify the column name.

ODI-15510
A column was not found while updating the key

Category:
Programmatic

Cause:
The update key contains a column that does not exist.

Action:
Check the columns of the update key.

ODI-15511
The join must be attached to the datastore to expand a lookup.

Category:
Programmatic

Cause:
The join is not attached to a datastore, so a valid lookup does not exist.

Action:
Only use the lookup expansion, with a pCreateLookup parameter value of false, on valid lookups.

ODI-15512
Cannot transform a normal datastore into a normal lookup.

Category:
Programmatic

Cause:
The data store is already a non-lookup data store.

Action:
Do not use this transformation on a non-lookup data store. If the datastore and join are non-lookup, use a pCreateLookup parameter value of true to create a lookup from a normal join and normal datastore.

ODI-15513
Cannot transform a normal, non-lookup join into a normal join.

Category:
Programmatic

Cause:
The join is already a normal join, not a lookup join, so expansion to a normal, non-lookup join is not possible.

Action:
Do not use this transformation on a normal join. If the datastore and join are non-lookup, use a pCreateLookup parameter value of true to create a lookup from a normal join and normal datastore.

ODI-15514
Cannot transform a lookup datastore into a lookup.

Category:
Programmatic

Cause:
The data store is already designated as a lookup, so transforming to a lookup is not possible.

Action:
Do not use this transformation on a lookup. If the datastore and join are designated for lookup, use a pCreateLookup parameter value of false to expand a lookup to a normal join and normal datastore.

ODI-15515
Cannot transform a lookup join into a lookup.

Category:
Programmatic

Cause:
The join is already designated as a lookup, so transforming to a lookup is not possible.

Action:
Do not use this transformation on a lookup. If the datastore and join are designated for lookup, use a pCreateLookup parameter value of false to expand a lookup to a normal join and normal datastore.

ODI-15516
The join must be attached to the datastore to make a lookup.

Category:
Programmatic

Cause:
The join is not properly attached to data sources, so transforming to a lookup is not possible.

Action:
Designate data sources for the join.

ODI-15517
Cannot add a column with the same name as an existing target column: {0}.

Category:
Programmatic

Cause:
The column being added already exists.

Action:
Add a column with a unique name.

ODI-15518
A dataset is already assigned the order: {0}.

Category:
Programmatic

Cause:
Another dataset has already been assigned the order that is being set.

Action:
Assign a unique order to the dataset.

ODI-15519
The target datastore cannot be changed. Interface {0} is used in interface(s) {1} as a source datastore.

Category:
Programmatic

Cause:
The interface is used as a source datastore of another interface, so the target datastore cannot be changed.

Action:
Create a separate interface to avoid the source datastore dependency in the other interface.

ODI-15520
Temporary interface from another project is not allowed.

Category:
Programmatic

Cause:
The interface is used as a source datastore of another interface, so the target datastore cannot be changed.

Action:
Create a separate interface to avoid the source datastore dependency in the other interface.

ODI-15521
A source datastore with alias {0} already exists.

Category:
Programmatic

Cause:
The datastore alias has already been used.

Action:
Specify a unique alias.

ODI-15522
Cannot transform a join into a CrossJoin or natural join if it does not have both attached datastores set.

Category:
Programmatic

Cause:
The join does not have datastores attached yet.

Action:
Attach both join datastores before transforming to a cross join.

ODI-15523
LKM {0} not accepted for source set {1}

Category:
Programmatic

Cause:
The LKM is not compatible with the source set technology or multi-connection setting.

Action:
Select an LKM which matches the source set technology and multi-connection setting.

ODI-15524
LKM {0} not accepted for staging area to target

Category:
Programmatic

Cause:
The LKM is not compatible with the staging area technology or multi-connection setting.

Action:
Select an LKM which matches the staging technology and multi-connection setting.

ODI-15525
CKM {0} not accepted for target technology

Category:
Programmatic

Cause:
The CKM is not compatible with the target technology.

Action:
Select a CKM which matches the target technology.

ODI-15526
IKM {0} not accepted for staging and target technology

Category:
Programmatic

Cause:
The IKM is not compatible with the staging or target technologies or multi-connection setting.

Action:
Select an IKM which matches the staging and target technologies and multi-connection setting.

ODI-15527
IKM {0} not accepted for target technology

Category:
Programmatic

Cause:
The IKM is not compatible with the target technology or multi-connection setting.

Action:
Select an IKM which matches the target technology and multi-connection setting.

ODI-15528
Mapping expression cannot be set because the target column {0} was not found.

Category:
Programmatic

Cause:
The column was not found when setting the expression for a mapping.

Action:
Specify a valid column for the expression.

ODI-15529
Action was not reversible.

Category:
Programmatic

Cause:
The actions causing an impact are not reversible.

Action:
Avoid the sequence of actions causing the impact.

ODI-15530
The interface does not have a source set.

Category:
Programmatic

Cause:
The interface does not have a source set.

Action:
Add a source set to the interface.

ODI-15531
The execution location parameter for the computeExpression method is invalid.

Category:
Programmatic

Cause:
The execution location parameter for the computeExpression method is invalid.

Action:
Specify an execution location parameter of ExecutionLocation.SOURCE, ExecutionLocation.WORK, or ExecutionLocation.TARGET.

ODI-15532
The pExecutableTextHolder parameter for the getLogicalSchemaForTextHolder method does not have a valid execution location.

Category:
Programmatic

Cause:
The pExecutableTextHolder parameter for the getLogicalSchemaForTextHolder method does not have a valid execution location.

Action:
Specify an execution location parameter of ExecutionLocation.SOURCE, ExecutionLocation.WORK, or ExecutionLocation.TARGET.

ODI-15533
The physical schema could not be mapped from logical schema {0} and context {1}.

Category:
Programmatic

Cause:
The getPhysicalSchema method failed to map and logical schema and context to a physical schema.

Action:
Ensure that logical to physical schema mappings are created or check the logical schema and context parameters.

ODI-15534
Sub interface must not be null.

Category:
Programmatic

Cause:
The pSubInterface parameter passed to the checkSubInterfaceValid method is null.

Action:
A non-null sub interface parameter is required for the checkSubInterfaceValid method.

ODI-15535
The technology {0} of the source temporary interface {1} used as a derived table does not support derived tables.

Category:
Programmatic

Cause:
The pSubInterface parameter passed to the checkSubInterfaceValid method is null.

Action:
A non-null sub interface parameter is required for the checkSubInterfaceValid method.

ODI-15536
Source temporary interface {0} cannot be used as a derived table. Its source datastore {1} defined in logical schema {2} has no associated physical schema in the optimization context {3}.

Category:
Programmatic

Cause:
The temporary interface cannot be used because a physical schema has not been mapped to the logical schema for the source.

Action:
Create a mapping between the logical schema, context, and physical schema for the source data store.

ODI-15537
Source temporary interface {0} cannot be used as a derived table. The logical schema of the target datastore {1} has no associated physical schema in context {2}.

Category:
Programmatic

Cause:
The temporary interface cannot be used because a physical schema has not been mapped to the logical schema for the target.

Action:
Create a mapping between the logical schema, context, and physical schema for the target data store.

ODI-15538
Source temporary interface {0} cannot be used as a derived table. The logical schema of the staging area {1} has no associated physical schema in the optimization context {2}.

Category:
Programmatic

Cause:
The temporary interface cannot be used because a physical schema has not been mapped to the logical schema for the staging area.

Action:
Create a mapping between the logical schema, context, and physical schema.

ODI-15539
Source temporary interface {0} cannot be used as a derived table. Source datastore {1} is not on the same data server as the target.

Category:
Programmatic

Cause:
The temporary interface cannot be used because the source data store is not on the same data server as the target.

Action:
Ensure that the source and target datastores are on the same data server.

ODI-15540
Source temporary interface {0} cannot be used as a derived table. Staging area and target datastores are not in the same data server. You may have forced the target context to a different context than the optimization context.

Category:
Programmatic

Cause:
The temporary interface cannot be used because the staging data store is not on the same data server as the target.

Action:
Ensure that the staging and target datastores are on the same data server.

ODI-15541
Source temporary interface {0} uses a journalized datastore and cannot be used as a derived table.

Category:
Programmatic

Cause:
The temporary interface cannot be used because it uses a journalized datastore.

Action:
Use only non journalized data stores in temporary interfaces.

ODI-15542
Source temporary interface {0} cannot be used as a derived table. All source datastores of this interface should be in the same data server as the target and should not be journalized.

Category:
Programmatic

Cause:
The temporary interface cannot be used because it uses a journalized datastore.

Action:
Use only non journalized data stores in temporary interfaces.

ODI-15543
Another interface with the same name already exists in this folder. Please choose a unique interface name.

Category:
Programmatic

Cause:
Another interface with the same name already exists in this folder.

Action:
Specify a unique interface name.

ODI-15544
The interface must have a name.

Category:
Programmatic

Cause:
The interface does not have a name.

Action:
Specify a unique interface name.

ODI-15545
Temporary target datastore has no name.

Category:
Programmatic

Cause:
The temporary target datastore has no name

Action:
Specify a unique datastore name.

ODI-15546
The interface must have a logical schema.

Category:
Programmatic

Cause:
The interface does not have a logical schema.

Action:
Specify a logical schema for the interface.

ODI-15547
Could not fix a missing reference correctly.

Category:
Programmatic

Cause:
The interface is missing one or more references.

Action:
Recheck target expressions for proper source references.

ODI-15548
The source datastore has already been set.

Category:
Programmatic

Cause:
The source datastore has already been set.

Action:
Only invoke setSourceDataStore once.

ODI-15549
Cannot set the source filter because the source datastore is not set.

Category:
Programmatic

Cause:
The source datastore has not been set prior to setting the filter.

Action:
Set the source datastore prior to setting the filter.

ODI-15550
The target datastore has already been set.

Category:
Programmatic

Cause:
The source datastore has already been set.

Action:
Only invoke setSourceDataStore once.

ODI-15552
A source filter requires a source datastore.

Category:
Programmatic

Cause:
The interface cannot be saved because it contains a filter without a source datastore.

Action:
Create a source datastore before creating a source filter.

ODI-15553
The target datastore must be set.

Category:
Programmatic

Cause:
The target datastore for the interface has not been set.

Action:
Set the target datastore before saving the interface.

ODI-15554
An LKM must be set on the source set.

Category:
Programmatic

Cause:
A loading knowledge module has not been assigned to the source set.

Action:
Set the LKM for the source set before saving the interface.

ODI-15555
Target IKM must be set on the target table.

Category:
Programmatic

Cause:
An integration knowledge module has not been assigned to the target table.

Action:
Set the IKM for the target before saving the interface.

ODI-15556
Unknown generic clause type: {0}

Category:
Programmatic

Cause:
An unknown generic clause class was passed to the createSnpPopClauseFromGenericClause method.

Action:
Pass only generic clause classes for join or filter.

ODI-15557
Unknown execution location type: {0}

Category:
Programmatic

Cause:
An unknown execution location enumeration was passed to the getStringExeDbFromExecutionLocation method.

Action:
Pass only location enumerations of ExecutionLocation.SOURCE, ExecutionLocation.WORK, ExecutionLocation.TARGET.

ODI-15558
There is a conflict between physical schemas

Category:
Programmatic

Cause:
There is a conflict between the various physical schemas used to obtain the data, such as multiple data stores in the same source set connected using different physical schemas.

Action:
Ensure that physical schemas of a source set have consistent connection information.

ODI-15559
Unsupported component: {0}

Category:
Programmatic

Cause:
An unsupported component was passed as a parameter to createDataAccessinfo.

Action:
For the pInterfaceSubComponents parameter, supported components are SourceDataStore, ISourceColumn, TargetMapping, and GenericClause.

ODI-15560
Fatal interface condition: {0}

Category:
Programmatic

Cause:
A fatal issue was discovered while saving or verifying an interface.

Action:
Correct the interface issue before saving it.

ODI-15561
Could not find column {0} which choosing a mapping.

Category:
Programmatic

Cause:
The MappingChooserFirst.chooseMapping method was called with an column name that does not exist.

Action:
Check the column name passed to chooseMapping.

ODI-15562
Source sets cannot be computed because one execution area doesn't have a physical schema. Check the errors on the interface.

Category:
Programmatic

Cause:
Source sets cannot be computed because one execution area doesn't have a physical schema.

Action:
Check the errors on the interface.

ODI-15563
Source sets cannot be computed because the staging area is not properly defined. Check your target datastore and the staging area's physical schema in the Definition tab.

Category:
Programmatic

Cause:
Source sets cannot be computed because the staging area is not properly defined.

Action:
Check your target datastore and the staging area's physical schema in the Definition tab.

ODI-15564
There should be one source set on the interface.

Category:
Programmatic

Cause:
The interface has more than one source set.

Action:
Ensure that only one source set is defined.

ODI-15565
Column {0} not found while setting the update key.

Category:
Programmatic

Cause:
A column specified for the update key does not exist.

Action:
Recheck the column names used to define the update key.

ODI-15566
No target column was found while setting the target data store.

Category:
Programmatic

Cause:
No target column was found while setting the target data store.

Action:
Define columns before setting the target datastore.

ODI-15567
Target column {0} was not found.

Category:
Programmatic

Cause:
No specified target column was not found in the target data store.

Action:
Check the column name parameter in the RealBasicInterfaceCreationHelper.getTargetColumn method call.

ODI-15568
Column {0} not found on datastore {1}.

Category:
Programmatic

Cause:
A referenced column was not found in a source data store.

Action:
Check the source datastore columns and references for a mismatch.

ODI-15570
Cannot add a datastore of type {0} as source.

Category:
Programmatic

Cause:
An invalid datastore type has been specified.

Action:
Specify a datastore of type TargetDataStore, SourceDataStore, or OdiDataStore.

ODI-15571
Unexpected join type {0}

Category:
Programmatic

Cause:
An invalid join type has been specified when setting join properties.

Action:
Specify a join type of INNER, CROSS, or NATURAL.

ODI-15572
Unexpected join state.

Category:
Programmatic

Cause:
An invalid join state has been reached. The expected join type is CROSS or NATURAL.

Action:
Review the error details for further information.v

ODI-15573
Failed to create an interface helper instance.

Category:
Programmatic

Cause:
A general exception was encountered while constructing an interface helper.

Action:
This is an internal error with no recommended user action.

ODI-15574
General exception encountered in the interface helper while preparing to persist.

Category:
Programmatic

Cause:
General exception encountered in the interface helper while preparing to persist.

Action:
This is an internal error with no recommended user action.

ODI-15575
Two journalized datastores have been found. There should be only one.

Category:
Programmatic

Cause:
Two journalized datastores have been found. There should be only one.

Action:
Remove jounalizing from one or more datastores.

ODI-15576
Two journalized filters have been found. There should be only one.

Category:
Programmatic

Cause:
Two journalized filters have been found. There should be only one.

Action:
Remove jounalizing from one or more datastores.

ODI-15577
Unmanaged type: {0}

Category:
Programmatic

Cause:
An invalid element type was passed to the prepareSQLStatement method.

Action:
Pass only valid element types such as GenericClause, SourceDataStore, TargetDataStore, ISourceColumn, TargetMapping, SourceSet, DataSet, or TargetColumn.

ODI-15578
No interface was found in the elements.

Category:
Programmatic

Cause:
No interface could be traced to the elements passed to the prepareSQLStatement method.

Action:
Create an interface.

ODI-15579
No dataset was found in the elements.

Category:
Programmatic

Cause:
No data set could be traced to the elements passed to the prepareSQLStatement method.

Action:
Ensure that a dataset has been created first.

ODI-15580
The target is a temporary table.

Category:
Programmatic

Cause:
The target datastore is a temporary target.

Action:
Use a non-temporary target.

ODI-15581
Cannot build the query because the ordered joins are not correct.

Category:
Programmatic

Cause:
The SQL clause cannot be generated because the ordered joins are not correct.

Action:
Ensure that all joins are correct.

ODI-15582
This operation is not supported on joined file datastores.

Category:
Programmatic

Cause:
Multiple source datastores were found.

Action:
Use only a single source datastore.

ODI-15583
This operation is not supported on multiple file datastores.

Category:
Programmatic

Cause:
More than one source datastore was found.

Action:
Use only a single source datastore.

ODI-15584
Elements are from different interfaces.

Category:
Programmatic

Cause:
The components passed to prepareSQLStatement are from different interfaces.

Action:
Only pass components from the same interface when preparing an SQL statement.

ODI-15585
Elements are from different datasets.

Category:
Programmatic

Cause:
The components passed to prepareSQLStatement are from different data sets.

Action:
Only pass components from the same data set when preparing an SQL statement.

ODI-15586
Unsupported component: {0}

Category:
Programmatic

Cause:
An invalid component type was passed to connectionForData.

Action:
Only pass components of type SourceDataStore, ISourceColumn, TargetMapping, TargetColumn, GenericClause, or TargetDataStore.

ODI-15587
Journalization filter not found for the journalized table.

Category:
Programmatic

Cause:
The journalized table does not have a filter.

Action:
Define a journalizing filter for the table.

ODI-15588
The SQL join clause is not valid for a cross join.

Category:
Programmatic

Cause:
A join clause has been specified for a cross join.

Action:
Remove the join condition or change the join type.

ODI-15589
Cannot change the ON_TARGET indicator on a temporary interface.

Category:
Programmatic

Cause:
An attempt was made to set the ON_TARGET indicator for a temporary datastore.

Action:
Do not change the ON_TARGET indicator for a temporary datastore.

ODI-15590
Unknown indicator type: {0}

Category:
Programmatic

Cause:
An unknown value was passed to the constructor for InterfaceActionOnStagingAreaSetIndicator.

Action:
Use valid values of DISTINCT_ROW, ON_TARGET, or ON_USER_DATABASE_SCHEMA for the pIndicatorType parameter.

ODI-15591
Staging Area is on the target and cannot be switched to another logical schema.

Category:
Programmatic

Cause:
The staging area is on the target and uses the target schema. It cannot be switched.

Action:
Do not attempt to switch the schema, or use a separate staging area.

ODI-15592
GenericClause is of unknown type: {0}

Category:
Programmatic

Cause:
InterfaceActionRemoveGenericClause was constructed with an invalid generic clause.

Action:
Use a generic clause type of JOIN or FILTER.

ODI-15593
Could not set LKM for object of type {0}

Category:
Programmatic

Cause:
An LKM is being set for a TargetDataStore or some other invalid type.

Action:
Only set an LKM for a SourceSet or StagingArea.

ODI-15594
Could not set the CKM for a holder of type {0}

Category:
Programmatic

Cause:
A CKM is being set for a SourceSet, StagingArea, or some other invalid type.

Action:
Only set a CKM for a TargetDataStore.

ODI-15595
Could not set the IKM for a holder of type {0}

Category:
Programmatic

Cause:
An IKM is being set for a SourceSet, StagingArea, or some other invalid type.

Action:
Only set an IKM for a TargetDataStore.

ODI-15596
Invalid KM type: {0}

Category:
Programmatic

Cause:
An invalid object type is being used to set a KM.

Action:
Only set a KM of type LKM, CKM, or IKM.

ODI-15597
Could not set the LKM option for a holder of type {0}

Category:
Programmatic

Cause:
An LKM is being set for a TargetDataStore or some other invalid type.

Action:
Only set an LKM option for a SourceSet or StagingArea.

ODI-15598
Could not set the CKM option for a holder of type {0}

Category:
Programmatic

Cause:
A CKM option is being set for a SourceSet, StagingArea, or some other invalid KM holder type.

Action:
Only set a CKM option for a KM holder of type TagetDataStore.

ODI-15599
Could not set the IKM option for a holder of type {0}

Category:
Programmatic

Cause:
An IKM option is being set for a SourceSet, StagingArea, or some other invalid KM holder type.

Action:
Only set an IKM option for a KM holder of type TagetDataStore.

ODI-15600
Dataset 1 was not found in the list of the interface datasets used with the interface.

Category:
Programmatic

Cause:
The first dataset given as a parameter in the construction of the InterfaceActionSwitchDataSetOrders class is not used in the interface.

Action:
Recheck the datasets being switched for this interface. Both datasets must be used in the interface.

ODI-15601
Dataset 2 was not found in the list of the datasets used with the interface.

Category:
Programmatic

Cause:
The second dataset given as a parameter in the construction of the InterfaceActionSwitchDataSetOrders class is not used in the interface.

Action:
Recheck the datasets being switched for this interface. Both datasets must be used in the interface.

ODI-15602
An unimplemented method has been called.

Category:
Programmatic

Cause:
An unimplemented method has been called.

Action:
Review the error details for information on the specific method call. Implement the method or call an alternative method.

ODI-15603
Cannot create an alias for a datastore of type {0}

Category:
Programmatic

Cause:
The method computeAliasForDataStore was called with an invalid datastore type.

Action:
Only call computeAliasForDataStore for datastores of type TargetDataStore or OdiDataStore.

ODI-15604
A non ordered clause was passed to the buildTreeSet method.

Category:
Programmatic

Cause:
A non ordered clause is passed to the construction of ordered joins trees method.

Action:
Use ordered join clauses with this method.

ODI-15605
Multiple ordered joins in this dataset use the same order number.

Category:
Programmatic

Cause:
One or more join clauses uses the same order number in the call to buildTreeSet.

Action:
Ensure that all clauses of an ordered join have unique order numbers.

ODI-15606
Join references the same table twice (directly or indirectly).

Category:
Programmatic

Cause:
A join clause contains two references to the same table.

Action:
Ensure that the join clause only references one table.

ODI-15607
Join references the same table twice through other joins.

Category:
Programmatic

Cause:
A join clause contains two references to the same table.

Action:
Ensure that the join clause only references one table.

ODI-15608
Subcomponent type of {0} is not supported.

Category:
Programmatic

Cause:
An unsupported type was passed to getIssuesComputer.

Action:
Only pass types of OdiInterface, DataSet, SourceDataStore, Filter, Join, StagingArea, TargetDataStore, SourceSet, TargetMapping, or TargetColumn.

ODI-15609
Invalid KM holder type: {0}

Category:
Programmatic

Cause:
An invalid KM holder type was passed to InterfaceKMHolderFactory.getKMHolderFor

Action:
Only pass KM holder types of SOURCE_SET_LKM, STAGING_AREA_LKM, TARGET_CKM, or TARGET_IKM.

ODI-15610
Component must be a source datastore or a source column.

Category:
Programmatic

Cause:
ReferenceManagerAbstract.getReferencesTo was called with an invalid subcomponent.

Action:
Only pass subcomponent types of SourceDataStore or ISourceColumn.

ODI-15611
Column not found from an xref.

Category:
Programmatic

Cause:
A column referenced in an expression was not found in a datastore. It may have been deleted.

Action:
Ensure that all columns referenced in the expression exist.

ODI-15612
Failed to attach an element of type {0} to a source set.

Category:
Programmatic

Cause:
An invalid type of component was found when attaching elements to a source set.

Action:
Elements being attached to a source set must be of type SourceDataStore, Join, Filter, or TargetMapping.

ODI-15613
Interface must have only one dataset.

Category:
Programmatic

Cause:
This sourceset computer can only handle a single dataset, and more than one was found.

Action:
Ensure that the interface uses only one dataset.

ODI-15614
Interface must have only one source table.

Category:
Programmatic

Cause:
This sourceset computer can only handle a single table, and more than one datastore was found.

Action:
Ensure that multiple tables are contained in a sourceset.

ODI-15615
Interface must not have joins.

Category:
Programmatic

Cause:
This sourceset computer can only handle a single table, and the interface contains a join.

Action:
Ensure that joins are contained in a sourceset.

ODI-15616
Source datastore must be a real table

Category:
Programmatic

Cause:
This sourceset computer can only handle a single, real table.

Action:
Ensure that only a single, real table is used in the sourceset.

ODI-15617
Invalid type for a TextHolder: {0}

Category:
Programmatic

Cause:
The method getExecutableTextHolderFor was called with an invalid TextHolder component type.

Action:
Valid types are TargetMapping, TargetColumn, Filter, and Join.

ODI-15618
Cannot set a source set on a target column.

Category:
Programmatic

Cause:
SetSourceSet was called for a target column, which is not a valid usage. This method is specified for the interface, but is not valid for this class.

Action:
SetSourceSet should never be invoked for this class.

ODI-15619
Inconsistent filter with a clauseType of {0}

Category:
Programmatic

Cause:
The Filter.getFilterType method was called, but the clause type was not a filter type.

Action:
Ensure that the filter has a type of SnpPopClause.CLAUSE_TYPE_FILTER or SnpPopClause.CLAUSE_TYPE_JRN_FILTER.

ODI-15620
Execution location is null. Target technology cannot be determined

Category:
Programmatic

Cause:
The execution filter for the location was not set.

Action:
The execution location should be set in the Filter constructor or by invoking setExecutionLocation.

ODI-15621
Attached dataStore is null. Target technology cannot be determined

Category:
Programmatic

Cause:
The attached datastore for the execution location was not set.

Action:
The datastore should be set in the Filter constructor or by invoking setAttachedDataStore.

ODI-15622
Staging area does not have a logical schema. Target technology cannot be determined

Category:
Programmatic

Cause:
The attached datastore for the execution location was not set.

Action:
The datastore should be set in the Filter constructor or by invoking setAttachedDataStore.

ODI-15623
Invalid technology for the given index type

Category:
Programmatic

Cause:
The technology of the clause and index type do not match.

Action:
Ensure that the index type technology matches the clause technology.

ODI-15624
Inconsistent join with clauseType = {0} and joinType = {1}

Category:
Programmatic

Cause:
The join clause type is invalid.

Action:
This exception is thrown from a deprecated method. Use isCross or isOrdered methods instead.

ODI-15625
Cannot set OdiDataType on a journalized source column

Category:
Programmatic

Cause:
The setDataType method has been invoked for a journalized source column, but the datatype cannot be set for journalized columns.

Action:
Do not invoke this method for a journalized column.

ODI-15626
Cannot set the length on a journalized source column

Category:
Programmatic

Cause:
The setLength method has been invoked for a journalized source column, but the length cannot be set for journalized columns.

Action:
Do not invoke this method for a journalized column.

ODI-15627
Cannot set the scale on a journalized source column

Category:
Programmatic

Cause:
The setScale method has been invoked for a journalized source column, but the scale cannot be set for journalized columns.

Action:
Do not invoke this method for a journalized column.

ODI-15628
Cannot set the data type on a source column

Category:
Programmatic

Cause:
The setDataType method has been invoked for a source column, but the datatype cannot be set for source columns.

Action:
Do not invoke this method for a source column.

ODI-15629
Cannot set the length on a source column

Category:
Programmatic

Cause:
The setLength method has been invoked for a source column, but the length cannot be set for source columns.

Action:
Do not invoke this method for a source column.

ODI-15630
Cannot set the scale on a source column

Category:
Programmatic

Cause:
The setScale method has been invoked for a source column, but the scale cannot be set for source columns.

Action:
Do not invoke this method for a source column.

ODI-15631
Connection information is not available.

Category:
Programmatic

Cause:
The physical schema has not been set.

Action:
Define physical and logical schemas.

ODI-15632
Column {0} may not be removed because it is mapped in interface {1}.

Category:
Programmatic

Cause:
The specified target column is mapped in another interface. This dependency prevents removal of the column.

Action:
Only remove a column after mapping dependencies have been removed.

ODI-15633
Data Type must be set first.

Category:
Programmatic

Cause:
Data Type is null.

Action:
Set Data Type.

ODI-15634
Length is not allowed for the current Data Type

Category:
Programmatic

Cause:
Data Type doesn't support length.

Action:
Check Data Type.

ODI-15635
Scale is not allowed for the current Data Type.

Category:
Programmatic

Cause:
Data Type doesn't support scale.

Action:
Check Data Type.

ODI-15636
Cannot change the column because it's not a temporary column.

Category:
Programmatic

Cause:
Column isn't temporary.

Action:
Check column state.

ODI-15637
Execution location must be either null or target.

Category:
Programmatic

Cause:
Wrong Execution location state.

Action:
Check Execution location.

ODI-15638
Scenario {0} contains invalid characters. Try {1}.

Category:
Other

Cause:
String contains invalid characters.

Action:
Check scenario name.

ODI-15639
Scenario version is not set.

Category:
Programmatic

Cause:
Scenario version is not set.

Action:
Set scenation version.

ODI-15640
No Scenario was found through the Tag : {0}.

Category:
Other

Cause:
No Scenario was found.

Action:
Check tag.

ODI-15641
The refresh SQL statement of a variable cannot contain sequence references when the variable is added to a load plan.

Category:
Programmatic

Cause:
SQL statement contains sequence references.

Action:
Check refresh SQL statement.

ODI-15642
Scenario name must be {0} characters long max.

Category:
Other

Cause:
Scenario name is too long.

Action:
Check name length.

ODI-15643
No Physical Mapping Design from Mapping: {0}.

Category:
Other

Cause:
Cannot find any Physical Mapping Design from Mapping.

Action:
Check there is valid Physical Mapping Design.

ODI-15644
The physical data server for the source code and for sequqnce(s) {0} is not the same, this may result in the same sequence value being used for each row.

Category:
Other

Cause:
The sequence may be remote so a single nextval is calculated and reused per row.

Action:
Make sure the sequence and task have the same data server if you want the sequences to use distinct values per row.

ODI-15645
The physical data server for the target code and for sequence(s) {0} is not the same, this may result in the same sequence value being used for each row.

Category:
Other

Cause:
The sequence may be remote so a single nextval is calculated and reused per row.

Action:
Make sure the sequence and task have the same data server if you want the sequences to use distinct values per row.

ODI-15700
Exception thrown in the Odi shortcut service: {0}

Category:
Programmatic

Cause:
An exception was thrown while materializing a shortcut object.

Action:
Check the root cause.

ODI-16000
Dataset has no sources: {0}

Category:
Programmatic

Cause:
The Dataset has no source or the source is not available.

Action:
Check sources.

ODI-16001
Dataset {0} contains only one source.

Category:
Programmatic

Cause:
The Dataset has only one source.

Action:
Check sources.

ODI-16002
Dataset has added default join condition with cartesian product: {0}

Category:
Programmatic

Cause:
Dataset has added default join condition with cartesian product.

Action:

ODI-16003
Multiple joins in the same dataset have the same order number: {0}

Category:
Programmatic

Cause:
Multiple joins in the same dataset have the same order number.

Action:
Check the order numbers of join components in the dataset.

ODI-16004
ANSI join: {0} has no user-defined order. The default order -1 (meaning "random order") is assigned.

Category:
Programmatic

Cause:
An ANSI join component does not have a join order assigned to it.

Action:
Assign an order number that is not -1.

ODI-16005
Join component inside dataset has no valid source references in the join condition. Join: {0} , condition = {1}.

Category:
Programmatic

Cause:
Join component inside dataset has no valid source references in the join condition.

Action:
Check source references in the join condition.

ODI-16006
Join component inside dataset has only one source references in the join condition, must have at least 2 references. Join: {0}, condition = {1}

Category:
Programmatic

Cause:
Join component inside dataset has only one source references in the join condition, must have at least 2 references.

Action:
Check join condition.

ODI-16008
There is no possible pairwise join order that satisfies both the join condition references and the user order numbers.

Category:
Programmatic

Cause:
There is no possible pairwise join order that satisfies both the join condition references and the user order numbers.

Action:
Check both the join condition references and the user order numbers.

ODI-16009
Lookup component creation is not complete: it misses either driving and/or lookup source information.

Category:
Programmatic

Cause:
Lookup component: {0} in dataset: {1} is incomplete. (Driving source: {2}, lookup source: {3})

Action:
Set the missing driving and/or lookup source on the lookup component.

ODI-16010
Dataset has sources that are not referenced by any join condition. Dataset: {0} , unconnected sources: {1}.

Category:
Programmatic

Cause:
Dataset has sources that are not referenced by any join condition.

Action:
Check sources.

ODI-16011
INTERNAL ERROR: Dataset error when connecting joins in order. Cannot find source for join: {0}, referenced source name: {1}.

Category:
Programmatic

Cause:
Dataset error when connecting joins in order. Cannot find source for join.

Action:
Check sources.

ODI-16012
Cannot find ordered join connection in dataset for: {0}

Category:
Programmatic

Cause:
Cannot find ordered join connection in dataset.

Action:
Check ordered join connection.

ODI-16013
Cannot find a valid pairwise tree of join connections for dataset: {0} unconnected join: {1} ({2})

Category:
Programmatic

Cause:
Cannot find a valid pairwise tree of join connections for dataset.

Action:
Check join connections.

ODI-16014
Cannot find a valid pairwise tree of join connections for dataset: {0}

Category:
Programmatic

Cause:
Cannot find a valid pairwise tree of join connections for dataset.

Action:
Check join connections.

ODI-16015
Missing expression for aggregate component {0}, attribute: {1}

Category:
Programmatic

Cause:
Missing expression for aggregator attribute.

Action:
Check aggregator attribute.

ODI-16016
Could not find an output signature for point: {0}

Category:
Programmatic

Cause:
Could not find an output signature for point.

Action:
Check output signature for the connection point.

ODI-16017
The join component: {0} has more than 2 input connector points. This is not recommended. ANSI SQL join syntax may not be supported.

Category:
Programmatic

Cause:
The join component has more than 2 input connector points. This is not recommended. ANSI SQL join syntax may not be supported.

Action:
Check the join component.

ODI-16018
The join condition for component: {0} only references {1} sources, but there are {2} input connector points. Expression text: {3}

Category:
Programmatic

Cause:
The number of references sources is less than the number of input connector points.

Action:
Check the join condition and input connector points.

ODI-16019
Set component output attribute {0} contains {1} expressions, but there are only {2} input connector points.

Category:
Programmatic

Cause:
The number of input expressions is greater than the number of input connector points.

Action:
Check expressions and input connector points.

ODI-16020
Set component output attribute expression for attribute: {0} does not have a scoping input connector point specified. Set component input expressions must have an associated scoping input connector point.

Category:
Programmatic

Cause:
A scoping input connector point need to be specified.

Action:
Check If set component input expressions have an associated scoping input connector point.

ODI-16021
The immediate downstream node {0} of the AP node {1}, which uses a push style LKM, is not a target.

Category:
Programmatic

Cause:
A push style LKM is assigned to an AP node but its immediate downstream node is not a target.

Action:
Either change the LKM to a pull style LKM or move some physical nodes to source execution unit(s).

ODI-16022
Set component output attribute: {0} does not have an expression that references through input: {1}.

Category:
Programmatic

Cause:
Not all input connector points have been referenced by one expression.

Action:
Check input connector points and expressions.

ODI-16023
Expression cross reference object is null: {0}.

Category:
Programmatic

Cause:
Expression cross reference object is null.

Action:
Check expression cross reference object.

ODI-16024
The expression contains unresolved attribute references. {0} Expression: {1} Unresolved identifiers: {2}.

Category:
Programmatic

Cause:
The expression contains identifiers that were not resolved as attribute references.

Action:
Check all identifiers in the expression for accessibility through a valid input connector point.

ODI-16025
An access point (AP) node has been created in the physical graph, but it does not have any columns: {0}.

Category:
Programmatic

Cause:
ERROR: An access point (AP) node has been created in the physical graph, but it does not have any columns.

Action:
Check access points.

ODI-16026
Cannot move an existing physical node to a different physical design! Node: {0}.

Category:
Programmatic

Cause:
Cannot move an existing physical node to a different physical design! .

Action:
The action attempted is not supported.

ODI-16027
No path exists from physical node: {0} to: {1}.

Category:
Programmatic

Cause:
No path exists between physical nodes.

Action:
Check paths between physical nodes.

ODI-16028
Expression push is not allowed because it would push the expression through projector node: {0}.

Category:
Programmatic

Cause:
Expression push is not allowed because it would push the expression through projector node.

Action:
The action attempted is not supported.

ODI-16029
Expression {0} ({1}) owned by: {2} has blank value, but a non-blank value is required.

Category:
Programmatic

Cause:
Expression has blank value, but a non-blank value is required.

Action:
Check the expression text.

ODI-16030
An attribute expression must reference only one projector or joiner source. Attribute: {0}.

Category:
Programmatic

Cause:
An attribute expression must reference only one projector or joiner source.

Action:
Check attribute expressions.

ODI-16031
The lookup component must have a driver and a lookup source input connection.

Category:
Programmatic

Cause:
The lookup component is not properly connected, it must have 2 input connections.

Action:
Connect the lookup component.

ODI-16032
Unsupported component type: {0}: component: {1} in dataset: {2}.

Category:
Programmatic

Cause:
The dataset does not support the component type.

Action:
Remove the component from the dataset.

ODI-16033
Aggregate filter: {0} is not supported in dataset: {1}.

Category:
Programmatic

Cause:
The dataset does not support aggregate filters.

Action:
Remove the aggregate filter.

ODI-16034
A transparent target LKM was picked for: {0}, but the AP node has more than one downstream target component.

Category:
Programmatic

Cause:
An AP node with a transparent target LKM can only have one downstream target.

Action:
Pick a different LKM.

ODI-16035
Target node {0} has assigned IKM {1}. The IKM will be ignored.

Category:
Programmatic

Cause:
A target node that is loaded by an upstream AP node with a transparent target LKM assigned does not need an IKM assigned, since the loading functionality will be handled by the LKM transparent push.

Action:
Set IKM to null.

ODI-16036
No target connected to AP node: {0} with SQL multi-connect LKM assigned.

Category:
Programmatic

Cause:
An AP node with SQL multi-connect LKM assigned has no target.

Action:
Add a target component.

ODI-16037
Only one target allowed for AP node: {0} with SQL multi-connect LKM assigned.

Category:
Programmatic

Cause:
An AP node with multi-connect LKM assigned cannot have multiple targets.

Action:
Pick different LKM, or remove all but one of the targets in the mapping.

ODI-16038
No extra logical components are allowed downstream from AP node: {0} with SQL multi-connect LKM assigned. The AP node must have a direct connection to target.

Category:
Programmatic

Cause:
An AP node with multi-connect LKM assigned must be connected directly to the target, with no intervening nodes.

Action:
Pick a different LKM, or reconfigure the physical graph such that the AP nodes connects directly to the target.

ODI-16039
The AP node: {0} has a transparent target LKM assigned, but it is not connected directly to the target.

Category:
Programmatic

Cause:
An AP node with transparent target LKM assigned must be connected directly to the target, with no intervening nodes.

Action:
Pick a different LKM, or reconfigure the physical graph such that the AP nodes connects directly to the target.

ODI-16040
Non-ANSI full outer join for component: {0} is not supported.

Category:
Programmatic

Cause:
Full outer join is set to generate non-ANSI syntax.

Action:
Check the box for "Generate ANSI Syntax" under Join properties.

ODI-16041
The manual group by clause is missing a required attribute: {0}

Category:
Programmatic

Cause:
The maual group-by expression is missing one or more attributes required for the SQL group-by clause.

Action:
Edit the manual group-by expression to included the missing attribute.

ODI-16042
The expression for attribute: {0} does not contain an aggregate function, but the group by column setting is NO. Non aggregate attributes should be part of the group-by clause.

Category:
Programmatic

Cause:
The group-by column setting for an attribute is NO, but it should be part of the group-by clause because the expression does not contain an aggregate function.

Action:
If the attribute expression does not contain an aggregate, set the group by column setting to YES.

ODI-16043
The expression for attribute: {0} contains an aggregate function, but the group by column setting is YES. Only non aggregate attributes should be included in the group-by clause.

Category:
Programmatic

Cause:
The group by column setting for an attribute is YES, but it should not be part of the group-by clause because the expression contains an aggregate function.

Action:
If the attribute expression contains an aggregate, set the group by column setting to NO.

ODI-16044
The having clause references aggregate attribute: {0}, but an aggregate function is not specified.

Category:
Programmatic

Cause:
An aggregated attribute is used in a having clause without an aggregate function.

Action:
If the having clause references an aggregated attribute, include the aggregate function used with that attribute.

ODI-16045
Input connector point {0} is not referenced by any attribute expression. That input to the set component is unused.

Category:
Programmatic

Cause:
An input connector point for a set component is unused because no attribute expressions reference attributes scoped through that connector.

Action:
At least one attribute expression should reference an attribute through the input connector in order to use that input to the set.

ODI-16046
Set components must have a minimum of two input connector points.

Category:
Programmatic

Cause:
The set component has less than two input connector points.

Action:
Add an input connector point. Set components must have at least two sources.

ODI-16047
Set component output attribute: {0} must have a non empty expression for input connector point {1}.

Category:
Programmatic

Cause:
The number of input expressions is less than the number of input connector points.

Action:
Specify a non empty expression for each input. Specify null if no attribute reference is used.

ODI-16048
Reusable mapping component: {0} must have a connection for input connector point {1}.

Category:
Programmatic

Cause:
An input connector point is not connected to another map component.

Action:
Connect the input connector point to a source component.

ODI-16049
Reusable mapping component {0} has one or more output connector points, but none are connected or contain target components. DML cannot be generated without a target component connected downstream or within the reusable mapping.

Category:
Programmatic

Cause:
None of the output connector points for the reusable mapping component are connected or contain target components.

Action:
Add a connection for at least one output connector point.

ODI-16050
Native sequence and ORDER BY operation are performed on the same flow. This might not be allowed in some technologies such as Oracle.

Category:
Programmatic

Cause:
Sequence is used before order by, this is now allowed in Oracle.

Action:
Remove sorter component or place sorter in an execution unit different from the sequence expression.

ODI-16051
The Sub select option may not be set for reusable mappings having an input signature.

Category:
Programmatic

Cause:
The reusable mapping component setSubSelect method was called with a value of true, but sub select is not allowed if an input signature is present.

Action:
Avoid calling the setSubSelect method or specify false for the value parameter.

ODI-16052
The Sub select option may not be set for reusable mappings having more than one output signature.

Category:
Programmatic

Cause:
The reusable mapping component setSubSelect method was called with a value of true, but sub select is not allowed if more than one output signature is present.

Action:
Avoid calling the setSubSelect method or specify false for the value parameter.

ODI-16053
Mixed non-ordered (outer) join and ordered join is not supported.

Category:
Programmatic

Cause:
Outer join is set to non-ordered.

Action:
Change the join to ordered join.

ODI-16054
An unparsed identifier, {0}, was found in the aggregate HAVING clause. This identifier was not found in any other aggregate or group by expressions.

Category:
Programmatic

Cause:
An identifier was found in the HAVING clause, but is invalid because it is not present in any aggregation or group by expression.

Action:
Remove this expression from the HAVING clause or use it in one of the aggregate output attribute expressions.

ODI-16055
Reusable mapping {0} for reusable mapping component {1} contains errors or warnings.

Category:
Programmatic

Cause:
A reusable mapping used by this mapping has errors or warnings.

Action:
See following error or warning messages regarding the reusable mapping.

ODI-16056
The driver connection for lookup component {0} is not connected to any source.

Category:
Programmatic

Cause:
A connection has not been made between the source and driving connection of the lookup component.

Action:
Connect a source to the lookup component driver connection.

ODI-16057
The lookup connection for lookup component {0} is not connected to any source.

Category:
Programmatic

Cause:
A connection has not been made between the source and lookup connection of the lookup component.

Action:
Connect a source to the lookup component lookup connection.

ODI-16058
Output signature {0} of reusable mapping {1} is not connected to any input source.

Category:
Programmatic

Cause:
An output signature is not connected to any upstream component.

Action:
Connect the output signature to an upstream component.

ODI-16059
Error adding lines to task container for KM {0}: {1}

Category:
Programmatic

Cause:

Action:

ODI-16060
Error finding helper component KM for AST processing of a node with 11g KM assigned: node={0}, helper KM={1}, error={2}

Category:
Programmatic

Cause:

Action:

ODI-16061
Error when calling generation delegate for component KM {0}: {1}

Category:
Programmatic

Cause:

Action:

ODI-16062
Cannot create node variable binding map for component KM {0}: {1}

Category:
Programmatic

Cause:

Action:

ODI-16063
No target multi-connect IKM found when processing an AP node with a SQL multi-connect LKM assigned.

Category:
Programmatic

Cause:
A multi-connect IKM could not be found for a target.

Action:
Check the target IKM assignment.

ODI-16064
When processing an AP node with SQL multi-connect LKM assigned, the downstream target node does not have a multi-connect IKM assigned.

Category:
Programmatic

Cause:
The IKM assigned to the target is not a multi-connect IKM. If an AP node uses a multi-connect LKM, a multi-connect IKM is required on the target.

Action:
Assign a multi-connect IKM to the target.

ODI-16065
Cannot get an entity manager for the mapping object. The entity manager must be set for the owning mapping or reusable mapping by calling IOdiEntityManager.persist() or Mapping.setEntityManager(), before this operation can be done. Mapping object= {0}

Category:
Programmatic

Cause:
An mapping operation is being performed that requires the mapping to resolve a reference, but the mapping entity manager has not been set.

Action:
Set the entity manager for the mapping, by calling IOdiEntityManager.persist() or Mapping.setEntityManager().

ODI-16066
Target datastore column {0} is a mandatory column and should be mapped.

Category:
Programmatic

Cause:
Missing expression for mandatory target datastore column.

Action:
Check target datastore mandatory column expression.

ODI-16067
The Sub select option may not be set for reusable mappings having no output signature.

Category:
Programmatic

Cause:
The reusable mapping component setSubSelect method was called with a value of true, but sub select is not allowed if no output signature is present.

Action:
Avoid calling the setSubSelect method or specify false for the value parameter.

ODI-16068
A parse error was encountered when parsing the expression: {0}. The default parser supports ANSI SQL delimiters. If a non-standard syntax is desired, use the free-form expression delimiters /%% and %%/ around the expression.

Category:
Programmatic

Cause:
Expression is syntactically incorrect.

Action:
Make sure the expression is well-formed.

ODI-16069
Technology {0} does not support the WHERE clause and cannot process the join.

Category:
Programmatic

Cause:
Technology "Where" indicator is set to false.

Action:
Check the technology setting or remove the join.

ODI-16070
Ordered joins are not supported in technology {0}.

Category:
Programmatic

Cause:
Technology Join Support Ordered indicator is set to false.

Action:
Set join to non-ordered (Generate ANSI syntax = false).

ODI-16071
Cross joins are not supported in technology {0}.

Category:
Programmatic

Cause:
Technology Cross Join indicator is set to false.

Action:
Set join type to non-cross join.

ODI-16072
Natural joins are not supported in technology {0}.

Category:
Programmatic

Cause:
Technology Natural Join indicator is set to false.

Action:
Set join type to non-natural join.

ODI-16073
Non-ordered natural joins are not supported.

Category:
Programmatic

Cause:
Natural Join is set to non-ordered (generate ANSI syntax = false).

Action:
Set 'Generate ANSI syntax' to true.

ODI-16074
Non-ordered joins are not supported in technology {0}.

Category:
Programmatic

Cause:
Join is set to non-ordered (generate ANSI syntax = false).

Action:
Set join to ordered (Generate ANSI syntax = true).

ODI-16075
Non-ordered outer joins are not supported in technology {0}.

Category:
Programmatic

Cause:
Outer Join is set to non-ordered (generate ANSI syntax = false).

Action:
Set 'Generate ANSI syntax' to true.

ODI-16076
Outer joins are not supported in technology {0}.

Category:
Programmatic

Cause:
Join is set to outer join.

Action:
Set join to non-outer join.

ODI-16077
Full outer joins are not supported in technology {0}.

Category:
Programmatic

Cause:
Join is set to full outer join.

Action:
Set join to non-full outer join.

ODI-16078
Inner joins are not supported in technology {0}.

Category:
Programmatic

Cause:
Join is set to inner join.

Action:
Set join to non-inner join.

ODI-16079
Reusable mapping {0} is not compatible with dataset {1}. A reusable mapping within a dataset must have no input signatures and exactly one output signature.

Category:
Programmatic

Cause:
An incompatible reusable mapping is being added to the dataset. The reusable mapping must have no input signatures and exactly one output signature.

Action:
Choose a different compatible reusable mapping or modify the resuable mapping to contain just a single output signature and no input signatures.

ODI-16080
Mapping component type {0} is not supported within a {1}.

Category:
Programmatic

Cause:
An unsupported component is being added to a mapping or composite component.

Action:
Use a supported component.

ODI-16081
Physical Mapping Design {0} cannot be calculated with no optimization context.

Category:
Programmatic

Cause:
The optimization context of the physical design is not set, or it becomes invalid because the referenced context is deleted.

Action:
Check the optimization context of the physical design and specify an appropriate context.

ODI-16082
The physical node {0} cannot be supported by technology {1} on execution unit {2} of mapping {3}.

Category:
Programmatic

Cause:
The physical node cannot be moved to the execution unit because its technology does not support the node.

Action:
Do not move the physical node to this execution unit.

ODI-16083
Input Attribute {0} of reusable mapping component {1} does not have an expression to connect it to any source, but is referenced in the reusable mapping.

Category:
Programmatic

Cause:
An input signature attribute in a reusable mapping is referenced by another component, but the input is not connected in the parent mapping.

Action:
Assign an expression to the reusable mapping component input attribute.

ODI-16084
The proposed connection would create a circular graph.

Category:
Programmatic

Cause:
The proposed connection would create a logical graph which contains a circular path, which connects a source component through some other components and back to itself.

Action:
Fix the connections to get rid of the circular path.

ODI-16085
Cannot set an expression for attribute {0} because the attribute was not found. Available attributes: {1}.

Category:
Programmatic

Cause:
SetAttributeExpressionText was called with an invalid attribute name.

Action:
Specify a valid attribute name.

ODI-16086
Set component {0} input connector point {1}: set operator {2} is not valid for {3} technology.

Category:
Programmatic

Cause:
The set operation chosen for the connector point is not valid for the technology.

Action:
Choose a set operation valid for the technology.

ODI-16087
Generation of set component {0} failed because of an incompatibility with the technology.

Category:
Programmatic

Cause:
The set operation chosen for the connector point is not valid for the technology.

Action:
Choose a set operation valid for the technology.

ODI-16088
Map component {0}, attribute {1} contains an aggregate function. Aggregate functions are only supported by the aggregate component.

Category:
Programmatic

Cause:
An aggregate function is used in the expression of a datastore attribute. The Datastore component does not support aggregate functions and will not generate the required GROUP BY clause.

Action:
Create an aggregate component to contain the aggregate function.

ODI-16089
"Cannot connect to component {0}, no input connector points are available.

Category:
Programmatic

Cause:
An attempt was made to connect to the component, but no input connector points are available.

Action:
Fix the connection graph.

ODI-16090
"Attempt connect a component to itself. from={0}, to= {1}

Category:
Programmatic

Cause:
An attempt was made to connect an output of the component back into an input of the same component.

Action:
Do not connect a component to itself.

ODI-16091
Expression component {0} has no attributes.

Category:
Programmatic

Cause:
An expression has no attributes. Expression components are projectors and must have attributes in order to be referenced by downstream components.

Action:
Add one or more attributes to the expression component.

ODI-16092
Datastore component {0}, attribute {1} is mandatory but not active.

Category:
Programmatic

Cause:
A datastore attribute is mandatory, but has been tagged as non active.

Action:
Set the mandatory attribute to active.

ODI-16093
The subselect option is not valid for reusable mapping component {0} because the reusable mapping contains an expression referencing a native sequence.

Category:
Programmatic

Cause:
The reusable mapping has an expression referencing a native sequence, and the subselect option has been chosen for the reusable mapping component.

Action:
Avoid using the subselect option for reusable mappings having expressions which reference native sequences.

ODI-16094
Physical node {0} is associated with logical schema {1}, but it is not mapped to a physical server in context {2}.

Category:
Programmatic

Cause:
The physical schema of the physical node cannot be resolved, as its logical schema is not mapped in the execution context.

Action:
Associate the logical schema with a physical schema in the context specified.

ODI-16095
"Scenario Generation failed for mapping {0} because no physical design was found.

Category:
Programmatic

Cause:
No physical design was found during scenario generation for a mapping.

Action:
Correct any errors preventing physical design generation.

ODI-16096
A mapping with name {0} already exists in folder {1}.

Category:
Programmatic

Cause:
A mapping with the same name already exist in the same folder.

Action:
Use a different name for the mapping.

ODI-16097
A reusable mapping with name {0} already exists in folder {1}.

Category:
Programmatic

Cause:
A reusable mapping with the same name already exist in the same folder.

Action:
Use a different name for the reusable mapping.

ODI-16098
A reusable mapping with name {0} already exists in global project.

Category:
Programmatic

Cause:
A reusable mapping with the same name already exist in the global project.

Action:
Use a different name for the reusable mapping.

ODI-16099
Name {0} already exists in {1} {2}.

Category:
Programmatic

Cause:
The given name is already used. Object name needs to be unique with the parent object.

Action:
Provide a different name for the object.

ODI-16100
Name cannot be an empty string.

Category:
Programmatic

Cause:
Name of an object cannot be empty.

Action:
Provide a name for the object.

ODI-16101
Name {0} contains invalid characters. Only letters, digits or underscore characters are allowed.

Category:
Programmatic

Cause:
Proposed name contains invalid characters, such as space. Only letters, digits or underscore characters are allowed.

Action:
Provide a different name for the object.

ODI-16102
Name {0} contains invalid characters. Only uppercase letters, digits or underscore characters are allowed, and the first character needs to be a letter.

Category:
Programmatic

Cause:
Proposed name contains invalid characters, such as space. Only uppercase letters, digits or underscore characters are allowed, and the first character needs to be a letter.

Action:
Provide a different name for the object.

ODI-16103
Name {0} is longer than {1} characters.

Category:
Programmatic

Cause:
Proposed name is too long.

Action:
Shorten the proposed name.

ODI-16104
The expression for attribute {0} cannot be resolved because it references an input signature which could not be redirected to an upstream expression. Input connector connections may be incorrect.

Category:
Programmatic

Cause:
An expression references an input signature, but it could not be redirected to an expression upstream of the input signature. Invalid input connector point connections are the most common cause.

Action:
Check all input connector points for correct upstream connections.

ODI-16105
Expression of attribute {0} does not refer to any upstream attribute.

Category:
Programmatic

Cause:
The expression is not set or the input connector point is not properly connected.

Action:
Verify the expression or the connection to the input connector point.

ODI-16106
No columns are set to update column in Target datastore {0}.

Category:
Programmatic

Cause:
The update indicator is not set in target datastore.

Action:
Verify the targetDatastore attribute and set the update indicator.

ODI-16107
The data type for datastore component {0}, attribute {1} is not defined.

Category:
Programmatic

Cause:
The data type of the column to which the datastore attribute is bound is null. This may occur when reverse engineering an unknown data type.

Action:
Add the data type to the technology and set the data type of the column.

ODI-16108
Preset Staging Location explicitly set to target location. This may result in the addition of another execution unit and decreased performance. Consider using the default Preset Staging Location, which is already set to use the target location.

Category:
Programmatic

Cause:
The preset staging location has been explicitly set, instead of using the default value. When an explicit value is set, and execution unit will be created, even if the location is the same as the target location.

Action:
Consider using the default value for the preset staging location.

ODI-16109
Encountered {0} at line {1} column {2}. Was expecting one of: {3}. The default parser supports ANSI SQL delimiters. If a non-standard syntax is desired, use the free-form expression delimiters /%% and %%/ around the expression.

Category:
Programmatic

Cause:
A parser error was encountered when parsing the expression.

Action:
Fix the syntax of the expression.

ODI-16110
Non-ANSI natural join for component: {0} is not supported.

Category:
Programmatic

Cause:
Natural join is set to generate non-ANSI syntax.

Action:
Check the box for "Generate ANSI Syntax" under Join properties.

ODI-16111
Cannot remove {0} connector point for component {1} due to minimum connector point count violation.

Category:
Programmatic

Cause:
Removal of connector point will result in connector point count less than minimum count.

Action:
Do not remove connector point.

ODI-16112
Reusable mapping component {0}, output connector point {1} is not connected.

Category:
Programmatic

Cause:
An output connector point of a reusable mapping component is not connected.

Action:
Check that connections from all output connector points are optional.

ODI-16113
Mapping component {0} has no input or output connections.

Category:
Programmatic

Cause:
An mapping component has not been connected.

Action:
Connect the component to a source and/or target component.

ODI-16114
Error when ordering the components for physical design:{0}, component re-ordering is not valid. A skipped component was not able to be placed in an execution unit because of dependency errors.

Category:
Programmatic

Cause:
When attempting to reorder the component nodes in the physical graph, an eror was found.

Action:
Do not reorder the component.

ODI-16115
Cannot reorder an outer join node around another kind of node.

Category:
Programmatic

Cause:
Cannot reorder an outer join node around another kind of node.

Action:
Cannot reorder an outer join node around another kind of node.

ODI-16116
Cannot reorder a join around another join if one of the joins does not have at least 2 references in its join condition.

Category:
Programmatic

Cause:
Illegal reordering.

Action:
Do not reorder the component.

ODI-16117
Cannot reorder a join around another join if one is generating ANSI and the other is not.

Category:
Programmatic

Cause:
Illegal reordering.

Action:
Do not reorder the component.

ODI-16118
Cannot reorder a join around another join if one is a left or right outer join and the other is not the same type, for non-ANSI joins.

Category:
Programmatic

Cause:
Illegal reordering.

Action:
Do not reorder the component.

ODI-16119
Cannot reorder a join around another join if either one is a left outer or right outer join, for ANSI joins.

Category:
Programmatic

Cause:
Illegal reordering.

Action:
Do not reorder the component.

ODI-16120
Warning: Target Load Order -- Child component is ordered before parent component.

Category:
Programmatic

Cause:
A datastore component with foreign key relationships is ordered before its parent datastore component.

Action:
Change the load order to put parent component before child component or keep the load order knowing that it may result in error in loading due to missing primary record.

ODI-16121
Error: Target Load Order -- Load order is not consistent with processing graph from source to target. Please modify the graph or change the load order.

Category:
Programmatic

Cause:
A target component is ordered before its source component.

Action:
Change the load order to put source component before target component or change the mapping design.

ODI-16122
Cannot create physical design due to mapping validation errors: {0}.

Category:
Programmatic

Cause:
Validation errors.

Action:
Fix the mapping.

ODI-16123
Node pushed upstream causes conflicts due to multiple upstream connections from different execution units. Pushed node={0}.

Category:
Programmatic

Cause:
Illegal node push.

Action:
Do not push the node to this location.

ODI-16124
Not allowed to reorder node {0}: {1}

Category:
Programmatic

Cause:
Illegal node push.

Action:
Do not push the node to this location.

ODI-16125
Not allowed to push node {0} past node {1}: {2}

Category:
Programmatic

Cause:
Illegal node push.

Action:
Do not push the node to this location.

ODI-16126
Physical graph re-ordering is causing a referencing problem for component: {0}.

Category:
Programmatic

Cause:
Illegal node push.

Action:
Do not push the node to this location.

ODI-16127
Cannot reorder component that is not a selector:{0}.

Category:
Programmatic

Cause:
Illegal node push.

Action:
Do not push the node to this location.

ODI-16128
Cannot reorder component that does not have at least one input and output connector point: {0}.

Category:
Programmatic

Cause:
Illegal node push.

Action:
Do not push the node to this location.

ODI-16129
Cannot reorder a component that has multiple downstream targets: {0}.

Category:
Programmatic

Cause:
Illegal node push.

Action:
Do not push the node to this location.

ODI-16130
Cannot reorder an outer join component: {0}.

Category:
Programmatic

Cause:
Illegal node push.

Action:
Do not push the node to this location.

ODI-16131
The node will not be moved.

Category:
Programmatic

Cause:
Illegal node push.

Action:
Do not push the node to this location.

ODI-16132
Cannot reorder node {0} downstream of {1}, since {1} has expression references to {0}.

Category:
Programmatic

Cause:
Illegal node push.

Action:
Do not push the node to this location.

ODI-16133
Cannot reorder node {0} upstream of {1}, since {0} has expression references to {1}.

Category:
Programmatic

Cause:
Illegal node push.

Action:
Do not push the node to this location.

ODI-16134
Cannot set journalizing for datastore component {0}, since its bound datastore is not journalized.

Category:
Programmatic

Cause:
Cannot set journalizing since the bound datastore is not journalized.

Action:
Make sure the bound datastore is CDC enabled.

ODI-16135
File technology has limited capability to serve as a staging area. Consider switching the staging area to another technology, such as in-memory engine.

Category:
Programmatic

Cause:
File technology unit set as staging area.

Action:
Set staging area to non-file technology.

ODI-16136
{0} {1} should not have a {2}. {2} will be ignored.

Category:
Programmatic

Cause:
With Join Type CROSS or NATURAL, the Join Condition will be ignored.

Action:
Check the Join Type. If correct, set the Join Condition to blank.

ODI-16137
IKM {0} is selected for physical node {1}, but the corresponding logical component {2} of reusable mapping {3} is not marked as derived sub-select.

Category:
Programmatic

Cause:
An IKM is used for extraction of a physical node, but derived sub-select is not enabled.

Action:
Change the KM selected for the physical node, or mark the logical component as derived sub-select.

ODI-16138
Internal error occurred during mapping metadata conversion. Please check the original 11g interface to see if it is complete and valid. Only interfaces that pass validation are supported during the upgrade process. If the 11g interface validates properly (in 11g) and then fails to upgrade cleanly, you should contact Oracle Support. The detailed exceptions information can be found in log file.

Category:
Programmatic

Cause:
Internal error occurred or unexpected exception received during mapping metadata conversion.

Action:
Make sure the original 11g interface is valid. If the 11g interface validates properly (in 11g) and then fails to upgrade cleanly, you should contact Oracle Support. The detailed exceptions information can be found in log file.

ODI-16139
Execution unit {0} does not have a location.

Category:
Programmatic

Cause:
The execution unit does not have a logical schema selected for its location.

Action:
Select a logical schema as the location of the execution unit.

ODI-16140
Mapping component {0} must have a connection for input connector point {1}.

Category:
Programmatic

Cause:
An input connector point is not connected to another map component.

Action:
Connect the input connector point to a source component.

ODI-16141
Mapping component {0} must have a connection for output connector point {1}.

Category:
Programmatic

Cause:
An output connector point is not connected to another map component.

Action:
Connect the output connector point to a downstream component.

ODI-16142
Cannot bind a datastore component to file model datastore {0}, use a file component instead.

Category:
Programmatic

Cause:
Attempt to bind a datastore component to a datastore with file technology.

Action:
Use a file component instead, and bind the file object to it.

ODI-16143
Cannot bind a file component to non-file model datastore {0}, use a datastore component instead.

Category:
Programmatic

Cause:
Attempt to bind a file component to a datastore with non-file technology.

Action:
Use a datastore component instead, and bind the file object to it.

ODI-16144
The expression cannot be pushed to execution unit {0} because its references would be out of scope.

Category:
Programmatic

Cause:
Illegal push-to target execution unit for expression.

Action:
Do not push the expression to this execution unit.

ODI-16145
The lookup match nth rows for lookup component {0} should be positive number.

Category:
Programmatic

Cause:
The match nth row property has not been correctly configured for lookup component.

Action:
Correct the match nth row property for lookup component.

ODI-16146
The join condition for component {0} contains a filter expression that does not reference a different schema on each side of the equality operator: {1}. Filter expressions may not behave as expected in joins.

Category:
Programmatic

Cause:
The join condition contains a filter expression. Filter expressions may not be effective in joins, and are inherently problematic in outer joins.

Action:
Move the extra filter condition to a separate filter component to eliminate interaction with the join.

ODI-16147
The join condition for component {0} does not contain an identifiable equality operator to join the input sources: {1}.

Category:
Programmatic

Cause:
The join condition may be missing an equality operator needed to match rows when joining the input sources.

Action:
Check the join expression for a valid equality operator.

ODI-16148
The size of map attribute {0} ({1}) is greater than the size of attribute {2} ({3}), to which it is mapped. Truncation or runtime errors are possible, depending on the technology.

Category:
Programmatic

Cause:
A map attribute is mapped to an attribute of smaller size. This may result in data truncation or DML errors.

Action:
Verify the size of both attributes and make any adjustments necessary to avoid truncation. Add an expression to explicitely truncate the data if necessary.

ODI-16149
For lookup component {0}, the option {1} for non matching rows may only be selected if option {2} is selected for multiple matching rows.

Category:
Programmatic

Cause:
The no match rows property has not been correctly configured for lookup component. It may only be used if the multiple matching rows option specifies all rows.

Action:
Correct the no match rows property for lookup component.

ODI-16150
Multiple non-ANSI outer joins exist within a dataset for the same datastore {0}.

Category:
Programmatic

Cause:
A datastore is outer joined to more than one datastore. This may result in execution errors.

Action:
Create joins outside of datasets.

ODI-16151
The context value {0} for map component {1} does not map to a physical location.

Category:
Programmatic

Cause:
The forced context value of a data storage component, combined with the model and logical schema, does not map to a physical schema. A map physical design cannot be created.

Action:
Use the logical schema editor or SDK to set a physcial schema for the chosen component context.

ODI-16152
Error processing KM target expression for mapping: {0}, KM line: {1}, KM error: {2}

Category:
Programmatic

Cause:
An exception was thrown during KM processing of the target expression for a particular line.

Action:
Review the KM line and error to determine the cause.

ODI-16153
Error processing KM source expression for mapping: {0}, KM line: {1}, KM error: {2}

Category:
Programmatic

Cause:
An exception was thrown during KM processing of the source expression for a particular line.

Action:
Review the KM line and error to determine the cause.

ODI-16154
No expressions have been defined on the attributes for map component {0}.

Category:
Programmatic

Cause:
A target datastore is connected, but none of its attributes have expressions defined.

Action:
Create expressions to map one or more attributes to a source.

ODI-16155
Join or Lookup component {0} is inactive. Components joining sources must be active.

Category:
Programmatic

Cause:
A join or lookup component has been set to inactive. Components which join sources must be active because all sources will not be in scope without the join.

Action:
Set the component to active.

ODI-16156
Join type {0} in {1} cannot be supported due to circular relationships in Dataset {2}.

Category:
Programmatic

Cause:
If a circle of relationships exist in a Dataset, one of the joinis must be reduced to a filter. The join type defined on it could be lost.

Action:
Examine the logic in the Dataset and try to reduce the number of outer joins if possible as the currently specified logic in Dataset cannot be translated to a SQL query.

ODI-16157
Ambiguous expression reference due to split path. {0} Expression: {1}, Available paths: {2}

Category:
Programmatic

Cause:
The connection path to the referenced attribute is split and the reference does not include a path specifier with a sufficient number of connector names to specify an unambiguous path..

Action:
Add a path specifier qualifier to the expression reference.

ODI-16158
Component in path specifier has multiple output connector points. {0} Expression: {1}, Component={2}

Category:
Programmatic

Cause:
A map component specified in the expression path specifier has multiple output connector points.

Action:
A specific connector point must be specified in the path specifier.

ODI-16159
Path specifier contains nonexistent identifier. {0} Expression: {1}, Identifier={2}

Category:
Programmatic

Cause:
An identifier specified in the expression path specifier is not found in the set of upstream components or connector points.

Action:
Fix the path specifier in the expression.

ODI-16160
Path specifier contains out-of-scope identifier. {0} Expression: {1}, Identifier={2}

Category:
Programmatic

Cause:
An identifier specified in the expression path specifier is not found in the set of upstream components or connector points.

Action:
Fix the path specifier in the expression.

ODI-16161
No matching path can be found. {0} Expression: {1}

Category:
Programmatic

Cause:
A path specifier is included in the expression, but it does not match any actual path in the map.

Action:
Fix the path specifier in the expression.

ODI-16162
Final parsing of {0} command {0} failed with exception {1}.

Category:
Programmatic

Cause:
A final parsing of the command was performed and hit an error.

Action:
Report as an ODI bug.

ODI-16163
Cannot parse identifier "{0}" because there are multiple instances of "{1}" in the mapping.

Category:
Programmatic

Cause:
An identifier in the expression can not be parsed because it refers to multiple components.

Action:
Fix the identifier in the expression.

ODI-16164
Internal Error: Cannot find input query select item with matching path specifier for expression cross reference: {0}

Category:
Programmatic

Cause:
The code generator cannot generate code for the map expression cross reference because the upstream query does not include the referenced object, with a matching path specifier.

Action:
Fix the expression.

ODI-16165
An attribute input expression for a set component must reference upstream attributes through only one input connector point. Attribute: {0}.

Category:
Programmatic

Cause:
An attribute input expression for a set component must reference upstream attributes through only one input connector point.

Action:
Check input expressions for the set component.

ODI-16166
Cannot parse the syntax of user defined function or language element {0}: {1}.

Category:
Programmatic

Cause:
The syntax text of the user defined function or language element cannot be parsed by the code generator.

Action:
Check the syntax text of the user defined function or language element.

ODI-16167
The function call {0} does not match the number of parameters defined for user defined function or language element {1}.

Category:
Programmatic

Cause:
The function call in the expression text does not match the number of parameters of the user defined function or language element.

Action:
Check the function call in the expression.

ODI-16168
Invalid parameter syntax in the syntax text of user defined function or language element {0}: {1}.

Category:
Programmatic

Cause:
One of the parameters in the syntax text contains invalid parameter syntax.

Action:
Check the syntax text of the user defined function or language element.

ODI-16169
Invalid parameter syntax in the implementation text of user defined function or language element {0}: {1}.

Category:
Programmatic

Cause:
One of the parameters in the implementation text contains invalid parameter syntax.

Action:
Check the implementation text of the user defined function or language element.

ODI-16170
Cannot locate calling parameter {0} in implementation text from the syntax text of user defined function or language element {1}.

Category:
Programmatic

Cause:
The calling parameter in the implementation text does not match any parameters that are defined in the syntax of the user defined function or language element.

Action:
Check the implementation text of the user defined function or language element.

ODI-16171
KM {0} is not valid for physical node {1}. The default KM is {2}.

Category:
Programmatic

Cause:
The KM being set is not valid for the physical node.

Action:
Set the KM using the default KM or another compatible KM.

ODI-16172
An expression in map component {0} cannot be resolved because it references an input signature which could not be redirected to an upstream expression. Input connector connections may be incorrect.

Category:
Programmatic

Cause:
An expression references an input signature, but it could not be redirected to an expression upstream of the input signature. Invalid input connector point connections are the most common cause.

Action:
Check all input connector points for correct upstream connections.

ODI-16173
Map component {0}, attribute {1} contains an expression which references a window function. Window functions are not valid for technology {2}.

Category:
Programmatic

Cause:
An attribute expression references a window or analytical function, but the technology does not support window functions.

Action:
Check the technology editor for window function support, and change the setting if the technology supports window functions. If not, the window function may not be used in the expression.

ODI-16174
Map component {0}, property {1} contains an expression which references a window function. Window functions are not valid for technology {2}.

Category:
Programmatic

Cause:
A property expression references a window or analytical function, but the technology does not support window functions.

Action:
Check the technology editor for window function support, and change the setting if the technology supports window functions. If not, the window function may not be used in the expression.

ODI-16175
Aggregate component {0}, attribute {1} contains an expression which references a window function. Window functions used within an aggregate component may result in errors or unexpected results.

Category:
Programmatic

Cause:
An attribute expression in an aggregate component references a window or analytical function. Due to rowset cardinality differences between window functions and aggregate functions, window functions may be problematic in the context of an aggregation.

Action:
Use window functions within a separate expression component.

ODI-16176
The filter condition for component {0} references a window function. Window function calls are not valid in filter conditions.

Category:
Programmatic

Cause:
A filter condition references a window or analytical function. Window functions are not valid in filter conditions.

Action:
Use window functions within a separate expression component upstream of the filter component.

ODI-16177
The join condition for component {0} references a window function. Window function calls are not valid in join conditions.

Category:
Programmatic

Cause:
A join condition references a window or analytical function. Window functions are not valid in join conditions.

Action:
Use window functions within a separate expression component upstream of the join component.

ODI-16178
The lookup condition for component {0} references a window function. Window function calls are not valid in lookup conditions.

Category:
Programmatic

Cause:
A lookup condition references a window or analytical function. Window functions are not valid in lookup conditions.

Action:
Use window functions within a separate expression component upstream of the lookup component.

ODI-16179
The subquery filter condition for component {0} references a window function. Window function calls are not valid in subquery filter conditions.

Category:
Programmatic

Cause:
A subquery filter condition references a window or analytical function. Window functions are not valid in subquery filter conditions.

Action:
Use window functions within a separate expression component upstream of the subquery filter component.

ODI-16180
The split condition for component {0}, output connector point {1} references a window function. Window function calls are not valid in split conditions.

Category:
Programmatic

Cause:
A split condition references a window or analytical function. Window functions are not valid in split conditions.

Action:
Use window functions within a separate expression component upstream of the split component.

ODI-16181
The expression for attribute {0}, connector point {1}, references a window function. Window functions may not be referenced in the subquery part of a subquery filter.

Category:
Programmatic

Cause:
An expression for an attribute that participates in the subquery part of a subquery filter references a window or analytical function. Window functions are not valid in expressions which are part of the filter in a subquery filter.

Action:
Use window functions within a separate expression component upstream of the subquery filter component.

ODI-16182
The expression for {0} references a native sequence, which is not supported for technology {1}.

Category:
Programmatic

Cause:
An expression for an attribute or property references a native sequence, but the execution technology does not support native sequences.

Action:
Remove the native sequence reference from the expression.

ODI-16183
Lookup component {0} specifies first, last, or nth row matching, but no order-by modifiers have been set on the attributes.

Category:
Programmatic

Cause:
No order by modifiers have been set for the lookup attributes.

Action:
Set an ASC or DESC order by modifier on one of the lookup attributes.

ODI-16184
Unable to fetch data from datastore {0}. The model {1} does not have a reverse-engineering context set.

Category:
Programmatic

Cause:
Context associated with the logical schema does not exist.

Action:
Check the context associated with the logical schema.

ODI-16185
{0} does not support single row selection from multiple matching rows.

Category:
Programmatic

Cause:
The database technology does not support the analytical functions used to select a particular matching row.

Action:
Select a lookup type which does not select a specified single row.

ODI-16186
Input attribute {0} has no expression, and no default value is defined in the corresponding input signature attribute. The input must have either a connected expression or a default value expression.

Category:
Programmatic

Cause:
The input attribute expression is not set and has no default value defined in the input signature attribute.

Action:
Verify the expression or add a default value in the input signature attribute expression.

ODI-16187
Dimension component {0} is not based on any dimension.

Category:
Programmatic

Cause:
Dimension component is not based on any dimension.

Action:
Dimension component should have base dimension.

ODI-16188
Dimension {1}, or its related structures on which component {0} is based, contains errors.

Category:
Programmatic

Cause:
One or more errors were found in the dimension or related structures that this dimension component is based on. These errors must be resolved.

Action:
Review the dimension and its related structures for possible errors.

ODI-16189
Dimension {1}, or its related structures on which component {0} is based, contains warnings.

Category:
Programmatic

Cause:
One or more warnings were found in the dimension or related structures that this dimension component is based on.

Action:
Review the dimension and its related structures for possible warnings.

ODI-16190
In dimension component {0}, the parent natural key attribute {2} of level {1} does not have expression.

Category:
Programmatic

Cause:
Parent natural key attribute does not have expression.

Action:
Set the expressions for parent natural key attributes.

ODI-16191
In dimension component {0}, the natural key attribute {2} of level {1} does not have expression.

Category:
Programmatic

Cause:
Natural key attribute does not have expression.

Action:
Set the expressions for natural key attributes.

ODI-16192
In dimension component {0}, no updatable attributes for level {1} have an expression. An updatable attribute is a non key attribute.

Category:
Programmatic

Cause:
No updatable attribute has an expression.

Action:
Set the expressions for updatable attributes.

ODI-16193
The value {0} for SCD type 2 gap is not valid.

Category:
Programmatic

Cause:
The value for SCD type 2 gap is not valid.

Action:
Set valid value for SCD type 2 gap.

ODI-16194
The value {0} for SCD type 2 gap unit is not valid.

Category:
Programmatic

Cause:
The value for SCD type 2 gap unit is not valid.

Action:
Set valid value for SCD type 2 gap unit.

ODI-16195
Cube component {0} is not based on any cube.

Category:
Programmatic

Cause:
A cube component must be based on a cube to be viable.

Action:
Associate the cube component to a cube.

ODI-16196
Cube {0}, or its related structures on which component {1} is based, contains errors.

Category:
Programmatic

Cause:
One or more errors were found in the cube or related structures (such as measures, dimensions, bound tables, etc.) that this cube component is based on. These errors must be resolved.

Action:
Review the cube and its related structures, such as dimensions and bound datastores, for possible errors.

ODI-16197
Cube {0}, or its related structures on which component {1} is based, contains warnings.

Category:
Programmatic

Cause:
One or more warnings were found in the cube or related structures (such as measures, dimensions, bound tables, etc.) that this cube component is based on.

Action:
Review the cube and its related structures, such as dimensions and bound datastores, for possible warnings.

ODI-16198
The dimension key attribute {0} in cube component {1} does not have an expression.

Category:
Programmatic

Cause:
The dimension key attribute in the cube component must have an expression.

Action:
Set an expression on each dimension key attribute.

ODI-16199
The null or invalid orphan policy for the base cube {0} is set to "default dimension record", but the "enable source aggregation" property on cube component {1} is set to false.

Category:
Programmatic

Cause:
The default dimension record orphan policy is set for the cube object, but source aggregation is not enabled on cube component.

Action:
If the default dimension record orphan policy is set for the cube object then it is recommended that source aggregation also be enabled on cube component. Otherwise the orphan management processing may produce multiple fact rows with the same default dimension references, which will cause an "unstable rowset" execution error in the database, since the dimension references are used as update match attributes for updating the fact table.

ODI-16200
At least one measure attribute in cube component {0} should have an expression.

Category:
Programmatic

Cause:
At least one measure attribute in the cube component should have an expression.

Action:
Set the expressions on the measure attributes.

ODI-16201
Not a known integration type for component {0}.

Category:
Programmatic

Cause:
The integration type for the cube component is invalid.

Action:
Set a valid integration type for the cube component.

ODI-16202
Not a valid attribute of component {0} or the attribute is not a measure.

Category:
Programmatic

Cause:
The specified attribute is not owned by the cube component or the attribute is not a measure.

Action:
Choose a measure attribute of the cube component.

ODI-16203
Not a valid attribute of component {0} or the attribute is not represented as a dimension natural key identifier.

Category:
Programmatic

Cause:
The specified attribute is not owned by the cube component or the attribute is not a dimension natural key identifier.

Action:
Choose a attribute of the cube component which is represented as a dimension natural key identifier.

ODI-16204
Dimension {0}, or its related structures on which component {1} is based, contains errors.

Category:
Programmatic

Cause:
One or more errors were found in the dimension or related structures that this dimension component is based on. These errors must be resolved.

Action:
Review the dimension and its related structures.

ODI-16205
The source aggregation function is not set for measure attribute: {0}, but the source aggregation is enabled on cube component {1}. Measure attribute will be included into GROUP BY clause.

Category:
Programmatic

Cause:
The source aggregation on the cube component is enabled, but no source aggregation function is specified on the measure attribute.

Action:
Specify a source aggregation function on the measure attribute or disable the source aggregation on the cube component.

ODI-16207
Not a known integration type for component {0}.

Category:
Programmatic

Cause:
Referencing a sequence from a different project is invalid.

Action:
Reset the dimension to use a sequence owned by the same project or a global sequence.

ODI-16208
In dimension {0} level {1}, level attribute {2} is defined as surrogate key, but its type is not NUMERIC.

Category:
Programmatic

Cause:
The level attribute is defined as surrogate key,but its datatype is not NUMERIC.

Action:
If the level attribute is defined as surrogate key, its datatype should be NUMERIC.

ODI-16209
Dimension {0} has some levels that use surrogate key but some that do not.

Category:
Programmatic

Cause:
The dimension has some levels that use surrogate key but some that do not.

Action:
Surrogate key usage must be consistent within a dimension. Modify the dimension to ensure all levels have a surrogate key or no levels have a surrogate key.

ODI-16210
In dimension {0}, level {1} does not use surrogate key and the natural key has more attribute defined.This is not supported by the dimension loading pattern.

Category:
Programmatic

Cause:
The level does not use surrogate key and the natural key has more than one attribute defined. This is currently not supported by the dimension loading pattern.

Action:
If no surrogate key is defined, the natural key should have only one attribute defined. Update the level accordingly.

ODI-16211
Dimension {0} uses surrogate key but is not associated with a sequence.

Category:
Programmatic

Cause:
The dimension uses a surrogate key but is not associated with a sequence.

Action:
Associate the dimension with a sequence or do not use a surrogate key.

ODI-16212
In dimension component {0} no SCD2 trigger attributes in level {1} have assignment expressions.

Category:
Programmatic

Cause:
In dimension component {0} no SCD2 trigger attributes in level {1} have assignment expressions.

Action:
Ensure one or more SCD2 trigger attributes have assignment expressions.

ODI-16213
In dimension {0} levels, both SCD2 and SCD3 parameters coexist.

Category:
Programmatic

Cause:
Some dimension attributes are using both SCD2 and SCD3 parameters across all dimension levels, this is not permitted.

Action:
Ensure that either SCD2 or SCD3 parameters are used across all dimension levels attributes, you cannot mix and match SCD2 and SCD3 parameters.

ODI-16222
In dimension {0} level {1}, level attribute {2} set the surrogate key bound column the same with primary key.

Category:
Programmatic

Cause:
The dimension level's surrogate key is bound to the primary key column. For this dimension pattern, that is not allowed.

Action:
For this dimension pattern, a surrogate key cannot be bound to a primary key column.

ODI-17500
Invalid old password.

Category:
Programmatic

Cause:
Old password did not match current password.

Action:
Provide the correct password.

ODI-17501
Temporary table has no column.

Category:
Other

Cause:
No column have been defined for the temporary table.

Action:
Define a column mapping to the temporary table.

ODI-17502
No next value returned.

Category:
Other

Cause:
No sequence next value was found for given context code.

Action:
Verify sequence definition or context code.

ODI-17503
Internal error: object ConnectConnection

Category:
Other

Cause:
Missed connection.

Action:
Try reconnect.

ODI-17504
An ordered join references the same table twice (directly or indirectly).

Category:
Other

Cause:
A same table was referenced twice by a join.

Action:
Check interface definition.

ODI-17505
An ordered join references the same table twice through another join.

Category:
Other

Cause:
A join was referencing the same table twice through another join.

Action:
Check interface definition.

ODI-17506
Variable has no value

Category:
Other

Cause:
Variable had no value.

Action:
Provide value for variable.

ODI-17507
Key does not exist

Category:
Other

Cause:
Key was unknown.

Action:
Provide a known key.

ODI-17508
No conversion for data type "{0}" from source technology "{1}" to destination technology "{2}"

Category:
Other

Cause:
No data type conversion between technology was found.

Action:
Define corresponding data type conversion.

ODI-17509
Query to access value for specific sequence {0} has failed. Query="{1}"

Category:
Other

Cause:
Query for sequence has failed.

Action:
Check sequence definition.

ODI-17510
Driver does not exist.

Category:
Other

Cause:
Driver was not found.

Action:
Check repository.

ODI-17511
No value to be set to variable "{0}".

Category:
Other

Cause:
No value was returned to be set to the variable.

Action:
Check variable value.

ODI-17512
Sequence is already locked

Category:
Other

Cause:
The sequence was already locked.

Action:
Unlock the sequence.

ODI-17513
Variable "{0}" does not exist.

Category:
Other

Cause:
Variable was not found.

Action:
Check variable.

ODI-17514
Unrecognized Oracle Data Integrator built-in function: {0}

Category:
Other

Cause:
Oracle Data Integrator built-in function was not recognized.

Action:
Check function syntax.

ODI-17515
Invalid loading command (INSERT,UPDATE...).

Category:
Other

Cause:
Loading command was invalid.

Action:
Check loading command.

ODI-17516
Internal error within the connection list

Category:
Other

Cause:
Internal error within the connection list.

Action:
Try again.

ODI-17517
Error during task interpretation. Task: {0} {1} Text: {2}.

Category:
Other

Cause:
A task interpretation error has occured.

Action:
Check tasks and try again.

ODI-17518
Error while interpreting the user name.

Category:
Other

Cause:
User name interpretation has failed.

Action:
Check user name.

ODI-17519
Error while interpreting the URL

Category:
Other

Cause:
URL interpretation has failed

Action:
Check URL.

ODI-17520
Error while interpreting the password

Category:
Other

Cause:
Password interpretation has failed.

Action:
Check password.

ODI-17521
Error while interpreting the driver

Category:
Other

Cause:
Driver interpretation has failed.

Action:
Check driver.

ODI-17522
Empty column name are not allowed

Category:
Other

Cause:
A empty column name was found.

Action:
Fill column name.

ODI-17523
There is no connection for this logical schema / context pair: {0} / {1}.

Category:
Other

Cause:
No connection was found for this logical schema / context pair.

Action:
Check schema and context assignment.

ODI-17524
Cannot set an empty alias for a source table.

Category:
Other

Cause:
Source table"s alias was empty.

Action:
Fill alias of source table.

ODI-17525
Cannot set an empty source set name.

Category:
Other

Cause:
Source set name was empty.

Action:
Fill alias of a source table.

ODI-17526
Cannot set Longc value in a PopCol having a column

Category:
Other

Cause:
Cannot set Longc value in a PopCol having a column.

Action:
Check interface`s columns.

ODI-17527
Cannot set SourceDt value in a PopCol having a column

Category:
Other

Cause:
Cannot set SourceDt value in a PopCol having a column.

Action:
Check interface`s columns.

ODI-17528
Cannot set Scalec value in a PopCol having a column

Category:
Other

Cause:
Cannot set Scalec value in a PopCol having a column.

Action:
Check interface`s columns.

ODI-17529
Reference check failure

Category:
Other

Cause:
Reference check has failed.

Action:
Check control conditions.

ODI-17530
Incomplete join may result in partial cross join

Category:
Other

Cause:
An incomplete join was found.

Action:
Check joins.

ODI-17531
KM already encrypted.

Category:
Other

Cause:
KM has been already encrypted.

Action:
Skip encryption.

ODI-17532
KM not encrypted.

Category:
Other

Cause:
KM was not encrypted.

Action:
Check KM.

ODI-17533
Clause set to cross join on a technology that does not support cross joins.

Category:
Other

Cause:
Technology did not support cross joins.

Action:
Correct joins.

ODI-17534
Clause set to full join on a technology that does not support full joins.

Category:
Other

Cause:
Technology did not support full joins.

Action:
Correct joins.

ODI-17535
Clause set to outer join on a technology that does not support left outer joins or right outer joins.

Category:
Other

Cause:
Technology did not support left outer joins.

Action:
Correct joins.

ODI-17536
Incomplete clause (Missing order number).

Category:
Other

Cause:
Order number was missing.

Action:
Correct clause.

ODI-17537
Incomplete clause (table1 and/or table2 must be set).

Category:
Other

Cause:
Table1 and/or table2 were undefined.

Action:
Set clause''s table1 and/or table2 tables.

ODI-17538
Filter is not properly set (The table must be defined)

Category:
Other

Cause:
The table must have been set.

Action:
Set filter''s table.

ODI-17539
Clause is ordered on a technology that does not support it

Category:
Other

Cause:
Technology did not support ordering.

Action:
Remove ordering.

ODI-17540
Connection is not set for this source set {0}.

Category:
Other

Cause:
Source set''s connection was not set.

Action:
Set connection.

ODI-17541
Method SnpTrt::getAllTrtOfTypeForTechnosAndProject requires not null parameters for technologies

Category:
Other

Cause:
Method requires not null parameters

Action:
Specify correct parameters.

ODI-17542
Sequence must be locked before using this function

Category:
Other

Cause:
Sequence was not locked.

Action:
Lock sequence and try again.

ODI-17543
Technology does not support joins

Category:
Other

Cause:
Technology did not support joins.

Action:
Check technology and/or joins.

ODI-17544
This Technology does not support the WHERE clause

Category:
Other

Cause:
Technology did not support the WHERE clause

Action:
Check technology and/or clause.

ODI-17545
Technology not set for this source set {0}

Category:
Other

Cause:
Source set''s technology was undefined.

Action:
Set technology.

ODI-17546
Specified variable not found in the Repository

Category:
Other

Cause:
Variable was not found in the Repository.

Action:
Define variable and try again.

ODI-17547
Data type "{0}" for the technology "{1}" does not exist.

Category:
Other

Cause:
Data type for the technology did not exist.

Action:
Check data type and/or technology.

ODI-17548
The file reverse-engineering is only possible for delimited files.

Category:
Other

Cause:
The file reverse-engineering was performed against a not delimited file.

Action:
Use delimited files.

ODI-17549
Source data type "{0}" for the technology "{1}" does not exist.

Category:
Other

Cause:
Source data type was not found.

Action:
Check data type and/or technology.

ODI-17550
Missing default Physical Schema for Data Server "{0}"

Category:
Other

Cause:
Default Physical Schema was undefined.

Action:
Specify default Physical Schema.

ODI-17551
Duplicate clause order numbers

Category:
Other

Cause:
Duplicated order numbers were found.

Action:
Check clause definition.

ODI-17552
Duplicate join order numbers

Category:
Other

Cause:
Duplicated join order numbers were found.

Action:
Check join.

ODI-17553
Exceeded the maximum number of errors allowed.

Category:
Other

Cause:
The maximum number of errors allowed were exceeded.

Action:
Check maximum error numbers.

ODI-17554
Agent "{0}" does not exist.

Category:
Other

Cause:
Agent was not found.

Action:
Check agent definition.

ODI-17555
You cannot unlock this object. Only the lock owners and Supervisors can unlock objects.

Category:
Other

Cause:
An attempt was made to unlock objects that were locked by another user.

Action:
Login as Supervisor or as the lock owners and try again.

ODI-17556
Error during decryption of text.

Category:
Other

Cause:
Text decryption has failed.

Action:
Try again.

ODI-17557
No condition defined for this rule.

Category:
Other

Cause:
No condition have been defined for this rule.

Action:
Define conditions.

ODI-17558
The field for this rule is not specified.

Category:
Other

Cause:
The field was unspecified.

Action:
Specify field for this rule.

ODI-17559
The operator for this rule is not specified.

Category:
Other

Cause:
The operator was unspecified.

Action:
Specify operator for this rule.

ODI-17560
The value to test is not defined.

Category:
Other

Cause:
The value to test was not defined.

Action:
Specify value.

ODI-17561
This operator is not supported.

Category:
Other

Cause:
This operator was not supported.

Action:
Correct operator.

ODI-17562
This operator cannot be used with this field.

Category:
Other

Cause:
The operator could not be used with the given field.

Action:
Correct operator.

ODI-17563
There is no work repository matching the name "{0}".

Category:
Other

Cause:
Work repository was not found.

Action:
Check work repository with the given name exists.

ODI-17564
More than one work repository found with the name "{0}" for this master repository.

Category:
Other

Cause:
More than one work repository with the specified name was found for this master repository.

Action:
Contact Oracle Support Services.

ODI-17565
Scenario has been already encrypted. No encryption was performed.

Category:
Other

Cause:
Scenario has been already encrypted.

Action:
Decrypt and try again.

ODI-17566
Scenario is not encrypted. No decryption was performed.

Category:
Other

Cause:
Scenario was not encrypted.

Action:
Check Scenario.

ODI-17567
A Scenario generated from a Variable cannot be encrypted or decrypted.

Category:
Other

Cause:
An attempt was made to encrypte or decrypte a Scenario generated from a Variable.

Action:
Change Scenario'' source component.

ODI-17568
Could not connect to the database referenced by the context and the logical schema

Category:
Network

Cause:
Connection to the database failed.

Action:
Check context and logical schema.

ODI-17569
Unable to update sequence''s next value.

Category:
Other

Cause:
Updating sequence was not possible.

Action:
Check sequence definition.

ODI-17570
Your text is too long. Please shorten it or choose the ''LONG TEXT'' datatype.

Category:
Other

Cause:
Text was too long.

Action:
Shorten the text or choose the LONG TEXT data type.

ODI-17571
Password does not respect the following rule: "{0}".

Category:
Security

Cause:
The password did not respect the rule.

Action:
Choose another password.

ODI-17572
This SnpFfValuee does not exist.

Category:
Other

Cause:
Value was not found.

Action:
Check FlexField value.

ODI-17573
This SnpFfValuem does not exist.

Category:
Other

Cause:
Value was not found.

Action:
Check FlexField value.

ODI-17574
This SnpFfValuew does not exist.

Category:
Other

Cause:
Value was not found.

Action:
Check FlexField value.

ODI-17575
SnpLicense does not exist.

Category:
Other

Cause:
SnpLicense was not found.

Action:
Check License.

ODI-17576
Unknown actual constraint type for an interface constraint.

Category:
Other

Cause:
Interface constraint type was unknown.

Action:
Check constraint type.

ODI-17577
Unknown variable data type.

Category:
Other

Cause:
Variable data type was unknown.

Action:
Check variable data type.

ODI-17578
Name "{0}" is already used.

Category:
Other

Cause:
Name was already used.

Action:
Use another name or change mode of import.

ODI-17579
Type of clause is not set.

Category:
Other

Cause:
Type of clause was not set.

Action:
Set type of clause.

ODI-17580
Type of join is not set.

Category:
Other

Cause:
Type of join was not set.

Action:
Set type of join.

ODI-17581
A non ordered clause is passed to the construction of ordered joins trees method.

Category:
Other

Cause:
A non ordered clause was passed to the construction of ordered joins trees method.

Action:
Check clauses.

ODI-17582
Missing order number for an ordered clause.

Category:
Other

Cause:
Clause order was not set.

Action:
Set the clause order.

ODI-17583
More than one unique constraint associated to an interface constraint.

Category:
Other

Cause:
More than one unique constraint associated to an interface constraint was found.

Action:
Check constraints.

ODI-17584
URL does not exist.

Category:
Other

Cause:
URL was not found.

Action:
Check URL.

ODI-17585
Key cannot be checked.

Category:
Other

Cause:
Key could not be checked.

Action:
Check key definition.

ODI-17586
Field separator is mandatory for a delimited file.

Category:
Other

Cause:
Field separator was missing.

Action:
Check separator and/or file type.

ODI-17587
Object name "{0}" is too long for the technology "{1}" (Logical schema : "{2}" ; Context Code : "{3}")

Category:
Other

Cause:
Object name was too long.

Action:
Correct object name.

ODI-17588
Unable to load work repository info.

Category:
Other

Cause:
Work repository was not found.

Action:
Contact Oracle Support Services.

ODI-17589
Logical schema has not been specified for sequence "{0}"

Category:
Other

Cause:
Logical schema was not specified.

Action:
Specify logical schema.

ODI-17590
Code {0} for model "{1}" is already used by another model.

Category:
Other

Cause:
An already used code was assigned.

Action:
Change code for model.

ODI-17591
Name "{0}" is already used.

Category:
Other

Cause:
A name already used was assigned.

Action:
Change name.

ODI-17592
Object is not in execution work repository.

Category:
Other

Cause:
Object was not in execution work repository.

Action:
Check object and/or repository.

ODI-17593
Maximum number or source/target technologies exceeded. Current limit is {0}.

Category:
Other

Cause:
Maximum number or source/target technologies was exceeded.

Action:
Check limit and number of technologies.

ODI-17594
Cannot encrypte already encrypted action.

Category:
Other

Cause:
This action has been already encrypted.

Action:
Skip encryption.

ODI-17595
This action is not encrypted.

Category:
Other

Cause:
This action was not encrypted.

Action:
Check parameters and try again.

ODI-17596
Query to retrieve value for native sequence "{0}" has failed Query="{1}"

Category:
Other

Cause:
Query has failed.

Action:
Check query.

ODI-17597
Cannot mix ordered and non-ordered join syntax within a dataset for technology.

Category:
Other

Cause:
Mixed join not allowed within a dataset.

Action:
Change all joins in dataset to same join syntax (either ordered or non-ordered).

ODI-17598
Non-ordered natural join is not supported.

Category:
Other

Cause:
Non-ordered natural join is not supported.

Action:
Change natural join to use ordered syntax.

ODI-17599
Ordered inner join is not supported.

Category:
Other

Cause:
Ordered inner join is disabled for technology.

Action:
Change join type.

ODI-17600
Ordered left outer join is not supported.

Category:
Other

Cause:
Ordered left outer join is disabled for technology.

Action:
Change join type.

ODI-17601
Ordered right outer join is not supported.

Category:
Other

Cause:
Ordered right outer join is disabled for technology.

Action:
Change join type.

ODI-17602
Non-ordered full outer join is not supported.

Category:
Other

Cause:
Non-ordered full outer join is not supported.

Action:
Change full outer join to use ordered syntax.

ODI-17603
Sql error checking a condition. {0}

Category:
Other

Cause:
Sql error checking a condition.

Action:
Correct the Sql in the condition.

ODI-17604
Reference column isn't associated with this instance of reference.

Category:
Programmatic

Cause:
Reference column isn't associated with this instance of reference.

Action:
Check reference column.

ODI-17605
Column is not associated to this datastore.

Category:
Programmatic

Cause:
Datastore doesn't have this column.

Action:
Check datastore and column.

ODI-17606
{0} already belongs to another OdiDataStore.

Category:
Programmatic

Cause:
Object belongs to another datastore.

Action:
Check object and datastore.

ODI-17607
Parameter pReference is not an outbound reference for this OdiDataStore.

Category:
Programmatic

Cause:
Parameter is not an outbound reference for OdiDataStore.

Action:
Check parameter.

ODI-17608
Invalid technology for the given data type.

Category:
Other

Cause:
Invalid technology for the given data type.

Action:
Check technology.

ODI-17609
Invalid data type code.

Category:
Programmatic

Cause:
Invalid data type code.

Action:
Check data type code.

ODI-17610
Found NULL in STEP_TYPE.

Category:
Programmatic

Cause:
Step type is null.

Action:
Check step type.

ODI-17611
STEP_TYPE is not valid.

Category:
Programmatic

Cause:
Step type isn't valid.

Action:
Check step type.

ODI-17612
MultiConnectionSupported is not settable for {0}.

Category:
Programmatic

Cause:
MultiConnectionSupported is not settable.

Action:
Check knowledge module.

ODI-17613
Cannot handle {0} of type {1}.

Category:
Programmatic

Cause:
Cannot handle object.

Action:
Check object's type.

ODI-17614
Unknown key type: {0}.

Category:
Programmatic

Cause:
Unknown key type.

Action:
Check key.

ODI-17615
The command is not an ODI Tool command.

Category:
Other

Cause:
Wrong command.

Action:
Check command.

ODI-17616
No WorkTextOrig was found for ID: {0}.

Category:
Other

Cause:
Invalid ID.

Action:
Check ID.

ODI-17617
Class descriptor for WorkTextOrig [{0}] is null.

Category:
Programmatic

Cause:
Descriptor is null.

Action:
Check class descriptors.

ODI-17618
Unable to deal with an AliasedColumnCrossRef with type {0}.

Category:
Programmatic

Cause:
Incorrect column type.

Action:
Check column type.

ODI-17619
Unexpected CrossRef {0} type.

Category:
Programmatic

Cause:
Incorrect CrossRef type.

Action:
Check CrossRef.

ODI-17620
Object type is not valid.

Category:
Programmatic

Cause:
Object type is not valid.

Action:
Check object type.

ODI-17621
Unable to manage crossRef for object from class [{0}].

Category:
Programmatic

Cause:
Illegal object type.

Action:
Check object type.

ODI-17622
pSqlIndGroup is not a valid group type.

Category:
Programmatic

Cause:
Invalid group type.

Action:
Check type.

ODI-17623
Too many parameters for function {0}, Object {1}, Language {2}.

Category:
Other

Cause:
Too many parameters.

Action:
Check parameters count.

ODI-17624
Missing parameter for function {0}, Object {1}, Language {2}.

Category:
Other

Cause:
Missing parameter.

Action:
Check parameters count.

ODI-17625
Only OdiColumns are currently supported for SnpsExpressionTag.

Category:
Programmatic

Cause:
Wrong column type.

Action:
Check column type.

ODI-17626
Cannot reassign a DataType.

Category:
Programmatic

Cause:
Technology has been assigned yet.

Action:
Check DataType

ODI-17627
Inconsistent connection settings.

Category:
Programmatic

Cause:
Inconsistent connection settings.

Action:
Check connection settings type.

ODI-17628
Unknown IConnectionSettings implementation.

Category:
Programmatic

Cause:
Unknown IConnectionSettings implementation.

Action:
Check settings type.

ODI-17629
Connection Settings for repository server must be instanceof JdbcSettings.

Category:
Programmatic

Cause:
Wrong settings type.

Action:
Check settings type.

ODI-17630
Unknown OptionType.

Category:
Programmatic

Cause:
Unknown OptionType.

Action:
Check option type.

ODI-17631
The given class has no matching OverridenOptionOrig.

Category:
Programmatic

Cause:
The given class has no matching OverridenOptionOrig.

Action:
Check class.

ODI-17632
Unexpected variable type.

Category:
Programmatic

Cause:
Unexpected variable type.

Action:
Check variable type.

ODI-17633
{0} datatype is expected.

Category:
Programmatic

Cause:
Wrong value datatype.

Action:
Check value datatype.

ODI-17634
Parameter must have text; it must not be null or empty.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17635
Parameter must have text; it must not be null, empty, or blank.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17636
Parameter {0} must be false.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17637
Parameter must not be null.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17638
Parameter {0} must be null.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17639
Parameter must be null.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17640
Parameter {0} must have text; it must not be null or empty.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17641
No {0} matches this IObject: {1}.

Category:
Programmatic

Cause:
IObject is not matched.

Action:
Check class.

ODI-17642
No Entity Class matches this Snp Class: {0}.

Category:
Programmatic

Cause:
No Entity Class matches Snp Class.

Action:
Check Entity Class.

ODI-17643
No Snp Class matches this Entity Class: {0}.

Category:
Programmatic

Cause:
No Snp Class matches Entity Class.

Action:
Check Snp Class.

ODI-17644
Unknown FlexFieldType.

Category:
Programmatic

Cause:
Unknown FlexFieldType.

Action:
Check FlexFieldType type.

ODI-17645
Parameter must be instance of {0}.

Category:
Programmatic

Cause:
Wrong parameter type.

Action:
Check parameter.

ODI-17646
It is forbidden to use a variable of one project in a package of another project.

Category:
Other

Cause:
Variable and package have different parents.

Action:
Check variable and package.

ODI-17647
Unable to create the expression element, Object {0}, Language {1}.

Category:
Other

Cause:
Unable to create the expression element.

Action:
Check expression parameters.

ODI-17648
A mapping cannot be on the target.

Category:
Other

Cause:
A mapping cannot be on the target.

Action:
Check execution location.

ODI-17649
Can't create join between 2 source datastore from different DataSet.

Category:
Other

Cause:
Source datastores are from different DataSet.

Action:
Correct join.

ODI-17650
A {0} was expected as value since {1} is {2}.

Category:
Other

Cause:
Wrong type.

Action:
Check type.

ODI-17651
Parameter {0} must be instance of [{1}].

Category:
Programmatic

Cause:
Wrong parameter class.

Action:
Check parameter class.

ODI-17652
Class {0} is not assignable to {1}.

Category:
Programmatic

Cause:
Inconsistent classes.

Action:
Check classes.

ODI-17653
{0} line isn't found.

Category:
Other

Cause:
Missed line.

Action:
Check line count.

ODI-17654
Parameter {0} must not be null.

Category:
Programmatic

Cause:
Parameter must be not null.

Action:
Check parameter.

ODI-17655
Parameter {0} must be {1} characters long max.

Category:
Programmatic

Cause:
Parameter length is too long.

Action:
Check parameter length.

ODI-17656
Can't define variable override for steps in exception tree.

Category:
Other

Cause:
Step is in exception tree.

Action:
Check step and variable for consistency.

ODI-17657
Cannot add a reference column to an OdiReference with type [{0}].

Category:
Other

Cause:
Reference type isn't ReferenceType.COMPLEX_REFERENCE.

Action:
Check reference type.

ODI-17658
Cannot change the target table because it's not a temporary datastore.

Category:
Other

Cause:
Datastore isn't temporary.

Action:
Check target table and datastore.

ODI-17659
Cannot get the journalized columns of a non-journalized datastore.

Category:
Programmatic

Cause:
Datastore isn't journalized.

Action:
Check datastore.

ODI-17660
Cannot set a clause on the target.

Category:
Other

Cause:
Wrong execution location.

Action:
Check execution location.

ODI-17661
{0} is not supported for this Technology.

Category:
Other

Cause:
Object is not supported for this Technology.

Action:
Check topology.

ODI-17662
Parameter {0} must have text; it must not be null, empty, or blank.

Category:
Programmatic

Cause:
Incorrect parameter.

Action:
Check parameter.

ODI-17663
Parameter {0} must be uppercase.

Category:
Programmatic

Cause:
Parameter is lower case.

Action:
Check parameter case.

ODI-17664
Parameter {0} must not contain whitespaces.

Category:
Programmatic

Cause:
Parameter contains whitespaces.

Action:
Consider to replace whitespace with another symbold (e.g. underscore)

ODI-17665
Column is not associated with this instance of OdiKey.

Category:
Other

Cause:
Column is not associated with instance of OdiKey.

Action:
Check column and OdiKey.

ODI-17666
Column is not present in the key.

Category:
Other

Cause:
Column is not present in the key.

Action:
Check column and key.

ODI-17667
Data type should be set before accessing value.

Category:
Programmatic

Cause:
Illegal method usage.

Action:
Set Data type.

ODI-17668
Datastore already has a Primary Key.

Category:
Other

Cause:
Datastore already has a Primary Key.

Action:
Remove the current primary key before adding a new one.

ODI-17669
{0} must be set before calling method {1}.

Category:
Programmatic

Cause:
Illegal method usage.

Action:
Set actual value.

ODI-17670
Default implementation already exists.

Category:
Programmatic

Cause:
Default implementation already exists.

Action:
Check function implementation.

ODI-17671
{0} must not be negative.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Set value to 0 or greater.

ODI-17672
FlexFields isn''t initialized.

Category:
Programmatic

Cause:
FlexFields isn''t initialized.

Action:
Call initFlexFields method first.

ODI-17673
Foreign key column''s datastore must be equals to this reference''s foreign datastore.

Category:
Other

Cause:
Inconsistent datastores.

Action:
Check datastore.

ODI-17674
IncrementValue is not set.

Category:
Programmatic

Cause:
IncrementValue is not set.

Action:
Set IncrementValue with setVariable method.

ODI-17675
Invalid step log's status.

Category:
Other

Cause:
Step status is not RUNNING.

Action:
Check step status.

ODI-17676
Invalid value type.

Category:
Programmatic

Cause:
Invalid value type.

Action:
Check value type.

ODI-17677
Cycle could be defined in {0} hierarchy.

Category:
Other

Cause:
It is forbidden to define cycle in {0} hierarchy.

Action:
Check hierarchy.

ODI-17678
It is forbidden to fill a key with columns from another datastore.

Category:
Other

Cause:
It is forbidden to fill a key with columns from another datastore.

Action:
Check datastore.

ODI-17679
It is forbidden to link two steps from different packages.

Category:
Other

Cause:
Steps are from different packages.

Action:
Check steps and packages.

ODI-17680
Line wasn't found.

Category:
Other

Cause:
Line wasn't found.

Action:
Check procedure lines.

ODI-17681
Maximum number of sessions must be positive.

Category:
Other

Cause:
Wrong value.

Action:
Check maximum number.

ODI-17682
Method is not valid unless MultiConnectionSupported.

Category:
Programmatic

Cause:
MultiConnectionSupported is true.

Action:
Check procedure.

ODI-17683
Model must be in Customized mode.

Category:
Other

Cause:
Wrong model mode.

Action:
Call setReverseType(ReverseType.CUSTOMIZED).

ODI-17684
Name can't be set.

Category:
Other

Cause:
Name is computed.

Action:
Check name.

ODI-17685
No {0} is defined for this model.

Category:
Other

Cause:
Missed definition.

Action:
Define CKM for model.

ODI-17686
No valid {0} name was found from this qualified name.

Category:
Other

Cause:
Valid name wasn't found.

Action:
Check qualified name.

ODI-17687
No valid qualified name was provided.

Category:
Other

Cause:
Name is invalid.

Action:
Check qualified name.

ODI-17688
OdiScenario is undefined.

Category:
Other

Cause:
OdiScenario is undefined.

Action:
Check OdiScenario definition.

ODI-17689
Option must be in the same procedure as line.

Category:
Other

Cause:
Option procedure is inconsistent.

Action:
Check option procedure.

ODI-17690
Package and procedure must be owned by the same project.

Category:
Other

Cause:
Procedure parent is inconsistent.

Action:
Check procedure parent.

ODI-17691
Primary key column's datastore must be equals to this reference's primary datastore.

Category:
Other

Cause:
Column datastore is inconsistent.

Action:
Check datastores.

ODI-17692
Reference column doesn't belong to this reference.

Category:
Programmatic

Cause:
Column is inconsistent.

Action:
Check column.

ODI-17693
Reference's foreign datastore is not equal to this datastore.

Category:
Programmatic

Cause:
Datastores are inconsistent.

Action:
Check datastores.

ODI-17694
Steps can't be moved from one package to another.

Category:
Other

Cause:
Steps can't be moved from one package to another.

Action:
Conside not to move steps.

ODI-17695
The new position is not valid.

Category:
Other

Cause:
The new position is not valid.

Action:
Check new position.

ODI-17696
The option already exists.

Category:
Other

Cause:
The option already exists.

Action:
Check option.

ODI-17697
The option owner has already been set.

Category:
Other

Cause:
The option owner has already been set.

Action:
Check option owner.

ODI-17698
The reference type must be [{0}] in order to define a complex SQL expression.

Category:
Programmatic

Cause:
Wrong reference type.

Action:
Check reference type.

ODI-17699
The reference type must be [{0}] in order to obtain the complex SQL expression.

Category:
Programmatic

Cause:
Wrong reference type.

Action:
Check reference type.

ODI-17700
The string value length should not exceed MAX_SHORT_TEXT_LENGTH since FlexFieldType is SHORT_TEXT.

Category:
Other

Cause:
FlexFieldType is SHORT_TEXT.

Action:
Check FlexFieldType and string value length.

ODI-17701
This OdiLoadPlanInstanceRun is not ESS Job related.

Category:
Other

Cause:
OdiLoadPlanInstanceRun is not ESS Job related.

Action:
Check OdiLoadPlanInstanceRun.

ODI-17702
This session is not ESS Job related.

Category:
Other

Cause:
Session is not ESS Job related.

Action:
Check session.

ODI-17703
This OdiReference must be from type [{0}] in order to access the primary DataStore alias.

Category:
Programmatic

Cause:
Wrong OdiReference type.

Action:
Check OdiReference type.

ODI-17704
This OdiReference must be from type [{0}] in order to set the primary DataStore alias.

Category:
Programmatic

Cause:
Wrong OdiReference type.

Action:
Check OdiReference type.

ODI-17705
This file descriptor is not consistent with the parent model's technology.

Category:
Other

Cause:
File descriptor is not consistent.

Action:
Check file descriptor and parent technology.

ODI-17706
This setVariable is used for increment.

Category:
Programmatic

Cause:
Increment value is set.

Action:
Use method getIncrementValue().

ODI-17707
Unable to add an alien main partition.

Category:
Other

Cause:
Main partition datastore is inconsistent.

Action:
Check main partition.

ODI-17708
Unable to compute name.

Category:
Programmatic

Cause:
Name has been set on this physical schema.

Action:
Do not compute name.

ODI-17709
Parameter must be false.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17710
Parameter {0} must be true.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17711
Undefined ODI work repository name.

Category:
Other

Cause:
Undefined repository name.

Action:
Check repository name.

ODI-17712
Variable and Step should be defined in the same Load Plan.

Category:
Other

Cause:
Variable and Step have different parent Load Plans.

Action:
Define variable and step in the same Load Plan.

ODI-17713
VariableDataType should be set before accessing DefaultValue.

Category:
Programmatic

Cause:
VariableDataType is undefined.

Action:
Set VariableDataType.

ODI-17714
You can only set KMs contained in the OdiProject containing of the OdiInterface.

Category:
Other

Cause:
KM has different parent project than OdiInterface.

Action:
Check KM.

ODI-17715
Can't add a null variable to load plan.

Category:
Programmatic

Cause:
Variable is null.

Action:
Check variable value.

ODI-17716
DataTypes must be consistent.

Category:
Other

Cause:
DataTypes is inconsistent.

Action:
Check DataTypes.

ODI-17717
Constraint is not a condition.

Category:
Programmatic

Cause:
Inconsistent constraint type.

Action:
Check parameter.

ODI-17718
Constraint is not a key.

Category:
Programmatic

Cause:
Inconsistent constraint type.

Action:
Check constraint.

ODI-17719
Option is not associated to this procedure.

Category:
Other

Cause:
Option is not associated to this procedure.

Action:
Check option and procedure.

ODI-17720
Constraint is not a reference.

Category:
Programmatic

Cause:
Inconsistent constraint type.

Action:
Check parameter.

ODI-17721
Parameter {0} already belongs to {1}.

Category:
Programmatic

Cause:
Parameter has parent.

Action:
Check parameter.

ODI-17722
Parameter {0} does not belong to this instance of {1}.

Category:
Programmatic

Cause:
Parameter has different parent.

Action:
Check parameter.

ODI-17723
Parameter {0} must belong to this {1}.

Category:
Programmatic

Cause:
Parameter parent is inconsistent.

Action:
Check parameter.

ODI-17724
Parameter {0} can't be moved to an other {1}.

Category:
Other

Cause:
Parameter can't be moved.

Action:
Do not move parameter.

ODI-17725
Parameter {0} must start with {1} prefix.

Category:
Other

Cause:
Parameter has wrong prefix.

Action:
Check parameter prefix.

ODI-17726
Logical Agent {0} must be mapped to a Physical Agent in the ContextCode {1}.

Category:
Other

Cause:
Agent is null.

Action:
Check agents.

ODI-17727
pDataServiceContainer is not a data service.

Category:
Programmatic

Cause:
pDataServiceContainer is not a data service.

Action:
Check pDataServiceContainer.

ODI-17728
Package and interface must be owned by the same project.

Category:
Other

Cause:
Package and interface have different parents.

Action:
Check package and interface.

ODI-17729
Parameter must be true.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17730
Not legal for shortcut.

Category:
Programmatic

Cause:
Object is shortcut.

Action:
Use getShortcutBaseObject() to access the real object.

ODI-17731
Not legal to construct a shortcut from a datastore in a model with a different technology.

Category:
Programmatic

Cause:
Inconsistent technologies.

Action:
Check model and datastore.

ODI-17732
Odi object Must be shortcut after materialize.

Category:
Programmatic

Cause:
Object isn't shortcut.

Action:
Check object.

ODI-17733
Reference's primary datastore must be not null in order to define a ReferenceColumn.

Category:
Programmatic

Cause:
Primary DataStore is null.

Action:
Check DataStore.

ODI-17734
pDataServiceContainer {0} has no technology defined.

Category:
Programmatic

Cause:
Data Service Container has no technology defined.

Action:
Define technology.

ODI-17735
Reference's foreign datastore is not equals to this datastore.

Category:
Programmatic

Cause:
Reference's foreign datastore is not equals to this datastore.

Action:
Check DataStores.

ODI-17736
You can only set global KMs or KMs contained in the OdiProject containing the OdiInterface.

Category:
Programmatic

Cause:
Wrong KM.

Action:
Check KM and project.

ODI-17737
StepLog and Variable don't belong to the same session.

Category:
Programmatic

Cause:
Inconsistent session.

Action:
Check Session value for StepLog and Variable.

ODI-17738
Unable to find '{0}' as variable used by the scenario '{1}' in version '{2}'.

Category:
Programmatic

Cause:
Variable is null.

Action:
Check variable name.

ODI-17739
Unable to override '{0}' variable for execution. It is marked as read-only for scenario '{1}' in version '{2}'.

Category:
Programmatic

Cause:
Variable is read-only.

Action:
Check variable.

ODI-17740
Error while connecting to the Application Server at URL {0}.

Category:
Network

Cause:
Exception was thrown during connection.

Action:
Ensure that the Application Server is running and accepting requests.

ODI-17741
Datastore isn't used as a lookup source.

Category:
Programmatic

Cause:
Datastore isn't used as a lookup source.

Action:
Check Datastore.

ODI-17742
Parameter {0} must be greater or equal than {1} and less or equal than {2}.

Category:
Programmatic

Cause:
Wrong parameter value

Action:
Check parameter.

ODI-17743
Variable should be related to the same {0}.

Category:
Programmatic

Cause:
Wrong parent for variable.

Action:
Check variable.

ODI-17744
The status can only be switched from ERROR to DONE or from DONE to ERROR.

Category:
Programmatic

Cause:
Wrong status

Action:
Check status.

ODI-17745
Parameter {0} must be greater or equal than {1}.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17746
Parameter {0} must be greater than {1}.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter.

ODI-17747
Array {0} must not be empty.

Category:
Programmatic

Cause:
Array length is 0.

Action:
Check array.

ODI-17748
Parameter {0} is not relevant to this schedule.

Category:
Programmatic

Cause:
Wrong parameter.

Action:
Check parameter.

ODI-17749
Invalid value was specified. Cannot create {0} with the value {1}.

Category:
Programmatic

Cause:
Invalid value was specified.

Action:
Check value.

ODI-17750
Parent folder already has the release tag set.

Category:
Programmatic

Cause:
Setting the release tag when the parent already has the release tag set.

Action:
Set the release tag in parent.

ODI-17751
Shortcut and the base object are under same folder.

Category:
Programmatic

Cause:
Cannot create shortcut {0} with the base object under same folder {1}.

Action:
Create shortcut in different folder.

ODI-17752
Shortcut and the base object are in different projects.

Category:
Programmatic

Cause:
Cannot create shortcut {0} in project {1} which is different from the project of the base object.

Action:
Create shortcut in same project as the base object.

ODI-17753
Shortcut with same reference object in same folder.

Category:
Programmatic

Cause:
There is other shortcut object with same reference object as {0} in the same folder.

Action:
Create shortcut in different folder.

ODI-17754
Shortcut and the base object are under same model.

Category:
Programmatic

Cause:
Cannot create shortcut {0} with the base object under same model {1}.

Action:
Create shortcut in different model.

ODI-17755
Shortcut with same reference object in same model.

Category:
Programmatic

Cause:
There is other shortcut object with same reference object as {0} in the same model.

Action:
Create shortcut in different model.

ODI-17756
Scenario "{0}", which is referenced by RunScenario step "{1}", has variable "{2}" but LoadPlan does not have variable with the same name.

Category:
Programmatic

Cause:
Missed variable in Load Plan

Action:
Check Load Plan''s variables.

ODI-17757
Scenario "{0}", which is referenced by RunScenario step "{1}", has a newer version "{2}" in the repository

Category:
Programmatic

Cause:
Scenario has newer version.

Action:
Consider to use latest version.

ODI-17758
LoadPlan Variable "{0}" SQL is different than the design repository Variable "{1}" SQL.

Category:
Programmatic

Cause:
Variable's SQL was redefined.

Action:
Check LoadPlan's variable.

ODI-17759
LoadPlan Variable "{0}" LogicalSchema "{1}" is different than the design repository Variable "{2}" LogicalSchema "{3}".

Category:
Programmatic

Cause:
Variable's Logical Schema was redefined.

Action:
Check LoadPlan's variable.

ODI-17760
Exception "{0}" is not used in the Load Plan.

Category:
Programmatic

Cause:
Exception is not used.

Action:
Consider to delete or disable unused exception.

ODI-17761
LoadPlan Variable "{0}" is refreshed at step "{1}", but it has no SQL.

Category:
Programmatic

Cause:
LoadPlan Variable doesn't have refresh SQL.

Action:
Check variable"s SQL or disable variable refreshing.

ODI-17762
Context is specified on a step "{0}", but it"s no longer present in the topology.

Category:
Programmatic

Cause:
Context was removed.

Action:
Check step's context.

ODI-17763
Logical Agent is specified on a step "{0}", but it is no longer present in the topology

Category:
Programmatic

Cause:
Logical Agent was removed.

Action:
Check step's Logical Agent.

ODI-17764
Context "{0}" and Logical agent "{1}" on a step "{2}" does not map to any physical agent.

Category:
Programmatic

Cause:
Physical Agent doesn"t exist.

Action:
Check agents" mapping.

ODI-17765
Scenario variable "{0}" type and LoadPlan variable "{1}" type mismatch.

Category:
Programmatic

Cause:
Variables have different datatype.

Action:
Check variables.

ODI-17766
Scenario "{0}" wasn"t found.

Category:
Programmatic

Cause:
Scenario doesn"t exist

Action:
Check scenario and Load Plan step.

ODI-17767
LoadPlan has variable "{0}", but repository doesn't have variable with the same name.

Category:
Programmatic

Cause:
Variable was deleted.

Action:
Check variables.

ODI-17768
LoadPlan Variable "{0}" has SQL, which could not be validated.

Category:
Programmatic

Cause:
OdiVariableTextGeneratorException during validation.

Action:
Check variable and variable text generator.

ODI-17769
OdiRef: Internal ID {0} of IObjects {1} should not be used when the repository is 12c mode.

Category:
Programmatic

Cause:
Internal ID is used in 12c mode.

Action:
Use Global Id instead of internal id.

ODI-17770
Profile {0} is not assigned to role {1}.

Category:
Security

Cause:
Profile is not assigned to role.

Action:
Check role's profiles.

ODI-17771
Enterprise principal with unique ID/name {0} is not mapped to role {1}.

Category:
Security

Cause:
Enterprise principal is not mapped to role.

Action:
Check role's mapped enterprise principals.

ODI-17772
Parameter {0} should be {1} or {2}.

Category:
Programmatic

Cause:
Wrong parameter value.

Action:
Check parameter value.

ODI-17773
Enterprise User or Role {0} does not exist.

Category:
Security

Cause:
Enterprise principla with such name could be found at LDAP server.

Action:
Check principal name and LDAP server.

ODI-17774
Maximum number of concurrent threads must be positive.

Category:
Other

Cause:
Wrong value.

Action:
Check maximum number provided.

ODI-17775
Maximum number of threads per session can not be negative.

Category:
Other

Cause:
Wrong value.

Action:
Check maximum number provided.

ODI-17776
Maximum number of concurrent threads must not be less than maximum session count.

Category:
Other

Cause:
Wrong value.

Action:
Check maximum numbers provided.

ODI-17777
Maximum number of threads per session must be not greater than maximum number of threads.

Category:
Other

Cause:
Wrong value.

Action:
Check maximum numbers provided.

ODI-17778
Maximum number of cache entries in Session Blueprint queue cannot be negative.

Category:
Other

Cause:
Wrong value.

Action:
Check value.

ODI-17779
Maximum idle time for Session Blueprint in cache cannot be negative.

Category:
Other

Cause:
Wrong value.

Action:
Check value.

ODI-17780
Package and mapping must be owned by the same project.

Category:
Other

Cause:
Package and mapping have different parents.

Action:
Check package and mapping.

ODI-17781
Physical Mapping Design must be owned by the mapping.

Category:
Other

Cause:
Physical Mapping Design is not owned by mapping.

Action:
Check mapping and physical design.

ODI-17782
OdiRef: Internal ID is retrieved in method {0}.{1} for 12c repository.

Category:
Programmatic

Cause:
Internal ID is retrieved in 12c mode.

Action:
Retrieve Global Id instead of internal id.

ODI-17783
Mapping metadata version mismatch. Expected {0}, but was {1}.

Category:
Other

Cause:
Mapping metadata version mismatch.

Action:
Check the expected and actual Mapping metadata version.

ODI-17784
Reusable Mapping metadata version mismatch. Expected {0}, but was {1}.

Category:
Other

Cause:
Reusable Mapping metadata version mismatch.

Action:
Check the expected and actual Reusable Mapping metadata version.

ODI-17785
Option positions in knowledge module must be unique.

Category:
Programmatic

Cause:
Option position undefined or multiple option in knowledge module has same position.

Action:
Modify the position of options to be unique and not null.

ODI-17786
JKM is not Oracle Golden Gate JKM.

Category:
Programmatic

Cause:
Model doesn't have JKM set or JKM is not Oracle Golden Gate JKM.

Action:
Set Oracle Golden Gate JKM for the model.

ODI-17787
Extract and initial extract processes cannot be the same.

Category:
Programmatic

Cause:
Extract and inital extract processes are the same.

Action:
Choose another extract or initial expract process.

ODI-17788
Replicat and initial replicat processes cannot be the same.

Category:
Programmatic

Cause:
Replicat and initial replicat processes are the same.

Action:
Choose another replicat or initial replicat process.

ODI-17789
Positions must be set positive.

Category:
Programmatic

Cause:
Position is not a positive integer.

Action:
Set the position to be a positive integer.

ODI-17790
{0} should be {1}

Category:
Programmatic

Cause:
Type is not correct

Action:
Set the correct type.

ODI-17791
The option group already exists.

Category:
Other

Cause:
The option group already exists.

Action:
Check option group.

ODI-17792
Option group is not associated to the same procedure

Category:
Other

Cause:
Group is not associated to the same procedure

Action:
Check option group.

ODI-17794
Count is larger than permissible value of Integer. Use method : {0}

Category:
Programmatic

Cause:
Return value is larger than permissible value of Integer

Action:
Use method : {0}

ODI-17795
{0} parameter is not valid

Category:
Programmatic

Cause:
Parameter is not correct

Action:
Set the correct parameter.

ODI-17796
{0} is not a valid technology.

Category:
Programmatic

Cause:
Technology is not correct.

Action:
Set the correct technology.

ODI-17797
Logical Agent "{0}" type and Physical Agent "{1}" type mismatch.

Category:
Programmatic

Cause:
Logical Agent and Physical Agent are of different type.

Action:
Check the type of Logical and Physical Agents.

ODI-17798
{0} parameter format is not valid.

Category:
Programmatic

Cause:
Parameter format is not correct.

Action:
Set the parameter with correct format.

ODI-17799
Level attribute {0} bound column: {1} is owned by table {2}, but the level is bound to table {3}

Category:
Programmatic

Cause:
The bound column parent table does not match the bound table for the level or dimension

Action:
Reset the column binding to a column of the bound level table.

ODI-17800
Level attribute {0} bound error column: {1} is owned by table {2}, but the level is bound to error table {3}

Category:
Programmatic

Cause:
The bound error column parent table does not match the bound error table for the level or dimension

Action:
Reset the error column binding to a column of the bound level error table.

ODI-17801
Level attribute {0} bound staging column: {1} is owned by table {2}, but the level is bound to staging table {3}

Category:
Programmatic

Cause:
The bound staging column parent table does not match the bound staging table for the level or dimension

Action:
Reset the staging column binding to a column of the bound level staging table.

ODI-17803
The dimension has an invalid cyclical parent/child level relationship involving {0}.

Category:
Programmatic

Cause:
One of the parent/child relationships reverses the order of another parent/child relationship, this is not allowed.

Action:
Fix the parent/child relationships for the dimension.

ODI-17804
The dimension hierarchy member uses parent ref {0}, which points to a level that is not included in the hierarchy.

Category:
Programmatic

Cause:
A dimension hierarchy must use parent references that allow navigation of the levels that are included in the hierarchy.

Action:
Fix the hierarchy member to use a different parent ref, or add a level to the hierarchy.

ODI-17805
An invalid dimension key for this key reference.

Category:
Programmatic

Cause:
The key reference must point to a dimension key which is belonged to the referenced dimension.

Action:
Use the dimension key belonged to the referenced dimension.

ODI-17806
The dimension key is already used by another key reference.

Category:
Programmatic

Cause:
Each dimension key can only be used by one key reference.

Action:
Set another dimension key that has not been used by any key reference.

ODI-17807
A non-transparent LKM must have a processing type of BOTH.

Category:
Programmatic

Cause:
The setProcessingType method was called for a LKM, and specified and incorrect type. A non-transparent LKM must have processing type of BOTH.

Action:
Change the call to set the correct type.

ODI-17808
Sql join parameter combination is not correct for technology {0}.

Category:
Programmatic

Cause:
Sql Join parameters combination is not correct.

Action:
Set the correct sql join parameter combination.

ODI-17809
When data server contains multiple schemas with same table and column names, physical schema must specify a schema name.

Category:
Other

Cause:
Schema name is not specified while creating the physical schema.

Action:
Please specify the schema name in corresponding physical schema.

ODI-17810
Error during BeanShell evaluation: {0}, Pre-execution code: {1}

Category:
Other

Cause:
Error occurs during BeanShell evaluation of procedure or KM task code.

Action:
Please check the procedure or KM task code in the error message.

ODI-17811
Supplied value {1} for flex field {0} is not a valid format.

Category:
Other

Cause:
Flex field value is not a valid format

Action:
Please provide the correct format.

ODI-17900
Cube {0} does not reference any dimensions.

Category:
Programmatic

Cause:
A cube must reference at least one dimension to be viable.

Action:
Add dimension references to the cube.

ODI-17901
Cube {0} does not have any measures.

Category:
Programmatic

Cause:
A cube must have at least one measure to be viable.

Action:
Define measures for this cube.

ODI-17902
A dimension reference of cube {0} is not associated with a level.

Category:
Programmatic

Cause:
A cube reference to a dimension must be associated with a level to be viable.

Action:
Ensure each dimension reference of the cube is associated with a level.

ODI-17903
Dimension {1} referenced by cube {0} is invalid.

Category:
Programmatic

Cause:
The cube references an invalid dimension.

Action:
Validate the dimensions which are referenced by this cube.

ODI-17904
Cube {0} has multiple references to dimension {1} with no unique role qualifiers.

Category:
Programmatic

Cause:
Role qualifiers are missing or not unique when a cube has multiple references to a dimension.

Action:
Set role qualifiers on the dimension references of the cube and ensure role qualifiers are unique.

ODI-17905
Cube {0} is not bound to a datastore.

Category:
Programmatic

Cause:
A cube must be bound to a datastore to be viable.

Action:
Bind the cube to a datastore.

ODI-17906
Cube {0} with orphan management enabled is not bound to an error datastore.

Category:
Programmatic

Cause:
A cube must be bound to an error datastore to be viable when orphan management is enabled.

Action:
Bind the cube to an error datastore.

ODI-17907
In cube {0}, measure {1} is not bound to a column of the cube bound datastore.

Category:
Programmatic

Cause:
The measure must be bound to a column of the cube bound datastore.

Action:
Bind each measure to a column of the cube bound datastore.

ODI-17908
In cube {0}, measure {1} is not bound to an error column of the cube bound error datastore when orphan management is enabled.

Category:
Programmatic

Cause:
The measure must be bound to an error column of the cube bound error datastore when orphan management is enabled.

Action:
Bind each measure to an error column of the cube bound error datastore.

ODI-17909
Cube {0} is bound to datastore {1}, but measure {2} is bound to column {3} which is owned by datastore {4}.

Category:
Programmatic

Cause:
The measure is bound to a column which is owned by a different datastore to the one bound to the cube.

Action:
Bind each measure to a column which is owned by the cube bound datastore.

ODI-17910
Cube {0} is bound to error datastore {1}, but measure {2} is bound to error column {3} which is owned by datastore {4}.

Category:
Programmatic

Cause:
The measure is bound to an error column which is owned by a different error datastore to the one bound to the cube.

Action:
Bind each measure to an error column which is owned by the cube bound error datastore.

ODI-17911
Cube {0} reference to dimension {1} does not have a key reference.

Category:
Programmatic

Cause:
The cube is missing a key reference for one of the dimensions.

Action:
Ensure the cube references the key for each dimension.

ODI-17912
Cube {0} reference to dimension {1}, level {2} has a surrogate key, but the key reference does not point to this surrogate key.

Category:
Programmatic

Cause:
The cube has a key reference that does not point to the surrogate key of the dimension level.

Action:
Ensure the cube references the surrogate key if the dimension level has a surrogate key.

ODI-17913
In cube {0}, the key reference for dimension {1} is not bound to a column of the cube bound datastore.

Category:
Programmatic

Cause:
The key reference for a dimension must be bound to a column of the cube bound datastore.

Action:
Bind each key reference to a column of the cube bound datastore.

ODI-17914
In cube {0}, the key reference for dimension {1} is not bound to an error column of the cube bound error datastore when orphan management is enabled.

Category:
Programmatic

Cause:
The key reference for a dimension must be bound to an error column of the cube bound error datastore when orphan management is enabled.

Action:
Bind each key reference to an error column of the cube bound error datastore.

ODI-17915
Cube {0} is bound to datastore {1}, but key reference for dimension {2} is bound to column {3} which is owned by datastore {4}.

Category:
Programmatic

Cause:
The key reference for a dimension is bound to a column which is owned by a different datastore to the one bound to the cube.

Action:
Ensure each key reference is bound to a column of the cube bound datastore.

ODI-17916
Cube {0} is bound to an error datastore {1}, but key reference for dimension {2} is bound to an error column {3} which is owned by datastore {4}.

Category:
Programmatic

Cause:
The key reference for a dimension is bound to an error column which is owned by a different datastore to the one bound to the cube.

Action:
Ensure each key reference is bound to an error column of the cube error bound datastore.

ODI-17917
In cube {0}, multiple dimension key references or measures are bound to the same column {1} of the cube bound datastore.

Category:
Programmatic

Cause:
Multiple dimension key references or measures of the cube are bound to a same column of the cube bound datastore.

Action:
Ensure each dimension key reference and each measure is bound to a separate column of the cube bound datastore.

ODI-17918
In cube {0}, multiple dimension key references or measures are bound to the same error column {1} of the cube bound error datastore.

Category:
Programmatic

Cause:
Multiple dimension key references or measures of the cube are bound to a same error column of the cube bound error datastore.

Action:
Ensure each dimension key reference and each measure is bound to a separate error column of the cube bound error datastore.

ODI-17919
There is no primary key to foreign key constraint defined in ODI between the cube table {0} and the dimension table {1}.

Category:
Programmatic

Cause:
ODI looks for primary key and foreign key references between dimension tables and cube tables. For cube table there is no foreign key to the dimension table.

Action:
Define a foreign key on the cube table that references the primary key on the dimension table.

ODI-17920
Dimension {0} does not have any levels.

Category:
Programmatic

Cause:
The dimension does not have any levels.

Action:
Create one or more levels for this dimension.

ODI-17921
In Dimension {0}, level {1} does not have any level attributes.

Category:
Programmatic

Cause:
The level does not have level attributes.

Action:
Create one or more level attributes for this level.

ODI-17922
In datastore {0}, attribute {1} is bound by more than one level attribute or parent reference members: {2}.

Category:
Programmatic

Cause:
One datastore attribute is bound by multiple level attributes or parent reference members; it should only be bound once.

Action:
Rebind the other level attributes or parent reference members to other datastore attributes.

ODI-17923
In Dimension {0}, hierarchy {1} contains either only one level or no levels.

Category:
Programmatic

Cause:
The hierarchy contains only one level or no levels.

Action:
The hierarchy should contain two or more levels.

ODI-17924
Dimension {0} has more than one level but no hierarchy defined.

Category:
Programmatic

Cause:
The dimension has more than one level but no hierarchy defined.

Action:
The dimension can have a single level with no hierarchies or all levels must be contained in at least one hierarchy.

ODI-17925
In dimension {0}, level {1} does not have any natural key.

Category:
Programmatic

Cause:
The level does not have any natural key.

Action:
Create a natural key for this level.

ODI-17927
In dimension {0}, level {1} does not have any updatable attributes. An updatable attribute is defined as level attribute that is not surrogate key or natural key.

Category:
Programmatic

Cause:
The level does not have any updatable attributes.

Action:
Define one or more updatable attributes for this level.

ODI-17929
Dimension {0} flagged as a star implementation is not bound to a datastore.

Category:
Programmatic

Cause:
The dimension flagged as a star implementation must be bound to a datastore.

Action:
Bind the dimension to a datastore.

ODI-17930
Dimension {0} is flagged as a snowflake implementation, but level {1} is not bound to a datastore.

Category:
Programmatic

Cause:
The dimension is flagged as a snowflake implementation, but the level is not bound to a datastore.

Action:
Bind the level to a datastore.

ODI-17931
In dimension {0}, level {1} is not bound to a staging datastore.

Category:
Programmatic

Cause:
The dimension level is not bound to a staging datastore.

Action:
Bind the level to a staging datastore.

ODI-17932
Dimension {0} is flagged as a star implementation and the orphan management is enabled, but the dimension is not bound to an error datastore.

Category:
Programmatic

Cause:
The dimension is flagged as a star implementation and the orphan management is enabled, but the dimension is not bound to an error datastore.

Action:
Bind the dimension to an error datastore.

ODI-17933
Dimension {0} is flagged as a snowflake implementation and the orphan management is enabled, but level {1} is not bound to an error datastore.

Category:
Programmatic

Cause:
The dimension is flagged as a snowflake implementation and the orphan management is enabled, but the level is not bound to an error datastore.

Action:
Bind the level to an error datastore.

ODI-17934
In dimension {0} level {1}, level attribute {2} is not bound to a column of the bound datastore.

Category:
Programmatic

Cause:
The level attribute is not bound to a column of the bound datastore.

Action:
Bind the level attribute to a column of the bound datastore.

ODI-17935
In dimension {0} level {1}, level attribute {2} is not bound to a staging column of the bound staging datastore.

Category:
Programmatic

Cause:
The level attribute is not bound to a staging column of the bound stating datastore.

Action:
Bind the level attribute to a staging column of the bound staging datastore.

ODI-17936
In dimension {0} level {1}, level attribute {2} is not bound to an error column of the bound error datastore.

Category:
Programmatic

Cause:
The level attribute is not bound to an error column of the bound error datastore.

Action:
Bind the level attribute to an error column of the bound error datastore.

ODI-17937
In dimension {0}, level {1} is bound to datastore {2}, but level attribute {3} is bound to column {4} which is owned by datastore {5}.

Category:
Programmatic

Cause:
The level is bound to a datastore, but a level attribute is bound to a column which is owned by another datastore.

Action:
Bind the level attribute to a column which is owned by the datastore that is bound to the level.

ODI-17938
In dimension {0}, level {1} is bound to staging datastore {2}, but level attribute {3} is bound to staging column {4} which is owned by datastore {5}.

Category:
Programmatic

Cause:
The level is bound to a staging datastore, but a level attribute is bound to a staging column which is owned by another datastore.

Action:
Bind the level attribute to a staging column which is owned by the staging datastore that is bound to the level.

ODI-17939
In dimension {0}, level {1} is bound to error datastore {2}, but level attribute {3} is bound to error column {4} which is owned by datastore {5}.

Category:
Programmatic

Cause:
The level is bound to an error datastore, but a level attribute is bound to an error column which is owned by another datastore.

Action:
Bind the level attribute to an error column which is owned by the error datastore that is bound to the level.

ODI-17941
Dimension {0} uses surrogate key but bound datastore {1} does not have primary key constraint.

Category:
Programmatic

Cause:
The dimension uses a surrogate key, but the datastore that is bound to the dimension does not have a primary key constraint.

Action:
Define a primary key constraint for the datastore that is bound to the dimension.

ODI-17942
Dimension {0} uses surrogate key but bound datastore {1} of level {2} does not have primary key constraint.

Category:
Programmatic

Cause:
The dimension uses a surrogate key, but the datastore that is bound to the level does not have a primary key constraint.

Action:
Define a primary key constraint for the datastore that is bound to the level.

ODI-17943
In dimension {0} level {1}, parent reference member {2} is not bound to a column.

Category:
Programmatic

Cause:
In the dimension, the parent ref member is not bound to a column.

Action:
Bind the parent reference member to a column.

ODI-17944
In dimension {0} level {1}, parent reference member {2} is not bound to a staging column.

Category:
Programmatic

Cause:
In dimension, the parent ref member is not bound to a staging column.

Action:
Bind the parent reference member to a staging column.

ODI-17945
In dimension {0} level {1}, parent reference member {2} is not bound to an error column.

Category:
Programmatic

Cause:
In dimension, the parent ref member is not bound to an error column.

Action:
Bind the parent reference member to an error column.

ODI-17946
In dimension {0} level {1} is bound to datastore {2}, but parent reference member {3} is bound to staging column {4} which is owned by datastore {5}.

Category:
Programmatic

Cause:
The level is bound to a datastore, but a parent reference member is bound to a column which is owned by another datastore.

Action:
Bind the parent reference member to a column which is owned by the datastore that is bound to the level.

ODI-17947
In dimension {0} level {1} is bound to staging datastore {2}, but parent reference member {3} is bound to column {4} which is owned by datastore {5}.

Category:
Programmatic

Cause:
The level is bound to a staging datastore, but a parent reference member is bound to a staging column which is owned by another datastore.

Action:
Bind the parent reference member to a staging column which is owned by the staging datastore that is bound to the level.

ODI-17948
In dimension {0} level {1} is bound to error datastore {2}, but parent reference member {3} is bound to error column {4} which is owned by datastore {5}.

Category:
Programmatic

Cause:
The level is bound to an error datastore, but a parent reference member is bound to an error column which is owned by another datastore.

Action:
Bind the parent reference member to an error column which is owned by the error datastore that is bound to the level.

ODI-17949
Dimension {0} is flagged as a snowflake implementation, in level {1}, the bound column of parent reference member {2} does not have foreign key constraint.

Category:
Programmatic

Cause:
The dimension is flagged as a snowflake implementation, in the level, the bound column of a parent reference member {2} does not have a foreign key constraint.

Action:
Define foreign key constraints for the columns that are bound to the parent reference members.

ODI-17950
In dimension {0} parent reference member {1}, the datatype of {3} of referenced level attribute {2} does not match with the datatype {5} of bound column {4}.

Category:
Programmatic

Cause:
For the parent reference member, the datatype of the referenced level attribute does not match with that of the bound column.

Action:
The datatype of the referenced level attribute should match with that of the bound datastore column.

ODI-17953
In dimension {0} parent reference member {1}, the datatype {3} of referenced level attribute {2} does not match with the datatype {5} of bound staging column {4}.

Category:
Programmatic

Cause:
For the parent reference member, the datatype of the referenced level attribute does not match with that of the bound staging column.

Action:
The datatype of the referenced level attribute should match with that of the bound staging datastore column.

ODI-17956
In dimension {0} parent reference member {1}, the datatype {3} of referenced level attribute {2} does not match with the datatype {5} of bound error column {4}.

Category:
Programmatic

Cause:
For the parent reference member, the datatype of the referenced level attribute does not match with that of the bound error column.

Action:
The datatype of the referenced level attribute should match with that of the bound error datastore column.

ODI-17959
Dimension {0} has an invalid cyclical parent/child level relationship involving parent reference {1}.

Category:
Programmatic

Cause:
One of the parent/child relationships reverses the order of another parent/child relationship, this is not allowed.

Action:
Fix the parent/child relationships for the dimension.

ODI-17960
In dimension {0} hierarchy {1}, the hierarchy member for level {2} uses parent reference {3}, which points to level {4} that is not included in this hierarchy.

Category:
Programmatic

Cause:
The hierarchy member uses the parent reference which points to the level that is not included in hierarchy.

Action:
Fix the hierarchy member to use a different parent reference or add a level to the hierarchy.

ODI-17961
In dimension {0} level {1}, the datatype {3} of level attribute {2} is does not match with the datatype {5} of bound column {4}.

Category:
Programmatic

Cause:
The datatype of the level attribute does not match with that of the bound column.

Action:
The datatype of the level attribute should match with that of the bound datastore column.

ODI-17964
In dimension {0} level {1}, the datatype {3} of level attribute {2} does not match with the datatype {5} of bound staging column {4}.

Category:
Programmatic

Cause:
The datatype of the level attribute does not match with that of the bound staging column.

Action:
The datatype of the level attribute should match with that of the bound staging datastore column.

ODI-17967
In dimension {0} level {1}, the datatype {3} of level attribute {2} does not match with the datatype {5} of bound error column {4}.

Category:
Programmatic

Cause:
The datatype of the level attribute does not match with that of the bound error column.

Action:
The datatype of the level attribute should match with that of the bound error datastore column.

ODI-17970
Dimension {0} is flagged as a star implementation, but parent reference {1} member {2} is not bound to the same column {3} as the matching parent level key attribute {4}.

Category:
Programmatic

Cause:
The dimension is star implementation, but one or more parent reference members is not bound to the same column as the matching parent level key attribute.

Action:
Bind the parent reference member to the column which is also bound to the matching parent level key attribute.

ODI-17971
In dimension {0} level {1}, attribute {2} is defined as a surrogate or natural key but is also flagged as having an SCD2 role (e.g. start date or trigger, etc.). This is not allowed.

Category:
Programmatic

Cause:
In SCD type 2, a key attribute cannot be flagged as a date or trigger attribute.

Action:
Do not define a key attribute as an SCD2 flag(e.g. date or trigger).

ODI-17972
In dimension {0}, if any of SCD2 trigger history, SCD2 effective time or SCD2 expiration time is set for a level {1}, then all of them must be set.

Category:
Programmatic

Cause:
In the dimension, if any of SCD2 trigger history, SCD2 effective time or SCD2 expiration time is set for a level, then all of them must be set.

Action:
Set SCD2 trigger history, SCD2 effective time and SCD2 expiration time for the level.

ODI-17973
In dimension {0}, SCD2 is enabled, but surrogate key is not used.

Category:
Programmatic

Cause:
In the dimension, SCD2 is enabled, but surrogate key is not used.

Action:
The dimension should use surrogate key if SCD2 is enabled.

ODI-17974
In dimension {0}, SCD2 is enabled for non-leaf level {1}, but hierarchy versioning is not enabled between level {1} and {2}. The versioning of non-leaf level {1} will not result in the versioning of its corresponding child records in level {2}.

Category:
Programmatic

Cause:
In the dimension, SCD2 is enabled for non-leaf level, but hierarchy versioning is not enabled.

Action:
Enable hierarchy versioning, otherwise the versioning of non-leaf level will not result in the versioning of its corresponding child records.

ODI-17975
In dimension {0} level {1}, a key attribute {2} is flagged as role playing(date or trigger, etc.). This is not allowed.

Category:
Programmatic

Cause:
In SCD type 3, a key attribute cannot be flagged as a date or trigger attribute.

Action:
Do not define a key attribute as an SCD3 flag(e.g. date or trigger).

ODI-17976
In dimension {0} level {1}, the datatype {3} of level attribute {2} does not match with the datatype {5} of SCD3 previous attribute {4}.

Category:
Programmatic

Cause:
In the dimension, the datatype of the level attribute does not match with that of the SCD3 previous attribute.

Action:
The datatype of the level attribute should match with that of the SCD3 previous attribute.

ODI-17979
Parameter {0} already exists

Category:
Programmatic

Cause:
Parameter {0} already exists

Action:
Use setValue() method to update the existing Parameter

ODI-17980
An operation with the name "{0}" already exists in "{1}".

Category:
Programmatic

Cause:
REST operation with same name.

Action:
Check REST operation name.

ODI-17981
REST operation with the name "{0}" does not exists in "{1}".

Category:
Programmatic

Cause:
REST operation does not exist.

Action:
Check REST operation name.

ODI-17982
Base KM type is incorrect.

Category:
Programmatic

Cause:
Base KM type is incorrect.

Action:
Set the Base KM with the correct type.

ODI-17983
It is not allowed for line defined in {0} referencing {1} line.

Category:
Programmatic

Cause:
Either line type is not same or the lines are self referencing.

Action:
Set the correct line.

ODI-17984
Line type is null.

Category:
Programmatic

Cause:
KM line type is null.

Action:
Set the correct line type.

ODI-17985
In dimension {0} level {1}, the attribute {2} is defined as part of the natural key, it cannot also be of type SCD3 at the same time.

Category:
Programmatic

Cause:
In the dimension, a level attribute is set as both natural key and SCD3 at the same time.

Action:
Either remove the SCD3 setting or remove this attribute from the natural key.

ODI-17986
In dimension {0} level {1}, level attribute {2} can not be flagged as an SCD3 previous value for more than one attribute nor as both a previous value and an effective date.

Category:
Programmatic

Cause:
In the dimension, a level attribute is set as an SCD3 previous value for more than one attribute or as both a previous value and as an effective date.

Action:
Correct the multiple SCD3 role uses of this attribute.

ODI-17987
In dimension {0} level {1}, level attribute {2} can not have both a SCD2 setting (date or trigger, etc.) and be used in an SCD3 role (previous value or effective date).

Category:
Programmatic

Cause:
In the dimension, a level attribute has both an SCD2 setting and is used in an SCD3 role.

Action:
Either remove this attribute's SCD2 setting or its uses as an SCD3 role.

ODI-17988
In dimension {0} level {1}, level attribute {2} can not have an SCD2 setting (date or trigger, etc.) and have SCD3 type attributes (previous value or effective date) set for it.

Category:
Programmatic

Cause:
In the dimension, a level attribute has an SCD2 setting and has SCD3 type attributes set for it.

Action:
Either remove this attributes SCD3 type attributes or remove its SCD2 setting.

ODI-17989
In dimension {0} level {1}, level attribute {2} can not be used as an SCD3 role attribute (previous value or effective date) and have SCD3 type attributes at the same time.

Category:
Programmatic

Cause:
In the dimension, a level attribute is used as an SCD3 role attribute and has SCD3 type attributes at the same time.

Action:
Either remove this attribute's SCD3 role usages or the SCD3 type attributes.

ODI-17990
In dimension {0}, level {1}, for level attribute {2} if the SCD3 effective date is set, the previous value must also be set.

Category:
Programmatic

Cause:
In the dimension, a level attribute has the SCD3 effective date set but has no previous value set.

Action:
Either remove this attribute's SCD3 effective date or add the SCD3 previous value.

ODI-17991
In dimension {0} level {1}, level attribute {2} is set as both the surrogate key and the natural key.

Category:
Programmatic

Cause:
In the dimension, can not set one attribute to surrogate key and natrual key both.

Action:
Reset either the surrogate key or the natural key.

ODI-17992
Model {0} is not a Generic Model

Category:
Programmatic

Cause:
Cannot map a Non-Generic Model to a Non-Generic Model

Action:
Provide a Generic Model to map

ODI-17993
Model {0} is not a Non-Generic Model

Category:
Programmatic

Cause:
Cannot map a Generic Model to a Generic Model

Action:
Provide a Non-Generic Model to map

ODI-17994
Invalid Sort by Position value: {0}

Category:
Programmatic

Cause:
Invalid value was provided for Hive Sort By Position

Action:
Provide a value >=1 or null

ODI-17995
This operation is not supported on {0} Technology

Category:
Programmatic

Cause:
This operation is not supported on the Technology of the Data Store

Action:
Please refer to documentation for supported Technologies

ODI-17996
Qualified Knowledge Module name {0} is invalid.

Category:
Programmatic

Cause:
KM qualified name is invalid

Action:
Provide a valid qualified KM Name

ODI-17997
Knowledge Module not found {0}

Category:
Programmatic

Cause:
KM with the given name not found

Action:
Provide a valid KM name

ODI-17998
Knowledge Module Line not found {0}

Category:
Programmatic

Cause:
KM Line with the given name not found

Action:
Provide a valid KM Line name

ODI-17999
Invalid language name or {0} Technology not set for KM.

Category:
Programmatic

Cause:
Language name is invalid or Technology not set for the KM.

Action:
Set valid language name and set KM source or target technology.

ODI-18000
In dimension {0} level {1}, the attribute {2} is defined as the surrogate key, it cannot also be of type SCD3.

Category:
Programmatic

Cause:
In the dimension, a level attribute is set as both surrogate key and SCD3 at the same time.

Action:
Remove the SCD3 setting from the surrogate key

ODI-18001
Cannot add new operation to BICS Physical Schema.

Category:
Programmatic

Cause:
User is trying to add new operation to BICS Physical Schema.

Action:
Adding new operation is not supported, please Contact Oracle support

ODI-18002
Cannot remove operation from BICS Physical Schema.

Category:
Programmatic

Cause:
User is trying to remove existing operation from BICS Physical Schema.

Action:
Removing operation is not supported, please Contact Oracle support

ODI-18003
Cannot delete mandatory property [{0}] from Data Server

Category:
Programmatic

Cause:
User is trying to delete a mandatory property from the Data Server

Action:
Mandatory properties cannot be deleted

ODI-18004
Invalid value specified for Data Server Property [{0}]. Permitted Values are: {1}

Category:
Programmatic

Cause:
User is trying to specify an invalid value for the Data Server property

Action:
Specify valid property value

ODI-18005
Language is not supported by the technology of this KM template or technology is not set for this KM template.

Category:
Programmatic

Cause:
Language is invalid for the technology set or technology not set for this KM template.

Action:
Set a language which is supported by the technology of this KM template.

ODI-18006
There are no unused levels remaining.

Category:
Programmatic

Cause:
No remaining levels to add to the hierarchy.

Action:
All levels are already part of this hierarchy.

ODI-18007
This level has no remaining parent references.

Category:
Programmatic

Cause:
All parent references for this level are already in use.

Action:
An unused parent reference is required in order to define a skip level.

ODI-18008
All attributes available for use in the natural key have already been set as members.

Category:
Programmatic

Cause:
There are no attributes remaining to participate in the natural key.

Action:
An unused attribute is required in order to add a natural key member.

ODI-18009
The line cannot be moved because the "before" or "after" line does not belong to this KM. A resolved base line is passed to the method.

Category:
Other

Cause:
Wrong KM line.

Action:
Check which KM owns the line.

ODI-18010
The "before" or "after" line has been deleted or is null. An invalid 'before' or 'after' line was passed to the move method.

Category:
Other

Cause:
Invalid line.

Action:
Check whether the line is not deleted or null

ODI-18011
Template Name "{0}" is already used with same combination of Technology and Language

Category:
Other

Cause:
A name already used with combination of same technology and Language

Action:
Change name.

ODI-18012
Failed to persist property {0} while persisting data server for Object Storage.

Category:
Other

Cause:
Contact Oracle support.

Action:
Contact Oracle support.

ODI-18013
Failed to retrieve credential information from Wallet for given connection information while creating Data Server

Category:
Security

Cause:
Contact Oracle support.

Action:
Contact Oracle support.

ODI-18014
Wallet file {0} is not found at specified location.

Category:
Security

Cause:
Wallet file is not present.

Action:
Please check Wallet file is present at specified location.

ODI-18015
Incorrect Wallet password.

Category:
Security

Cause:
Provided Wallet password is incorrect.

Action:
Please enter correct Wallet password.

ODI-18016
Wallet file {0} is not accessible .

Category:
Security

Cause:
Wallet file is not accesible.

Action:
Please check Wallet file permission.

ODI-18017
Invalid Credential file type : {0}. Please upload valid Credential file.

Category:
Security

Cause:
Credential file is not valid.

Action:
Please upload valid Credential file.

ODI-18018
Wallet file {0} does not contain credentials for given connection information.

Category:
Security

Cause:
Wallet file doesnot have required information.

Action:
Please add credential information to Wallet file for given connection information.

ODI-18019
Credential file {0} does not contain connection information.

Category:
Security

Cause:
tnsnames.ora file doesnot have required information.

Action:
Please add required connection information.

ODI-18020
Credential file {0} is not accessible.

Category:
Security

Cause:
Credential file doesnot have required permission.

Action:
Please add required permission.

ODI-18021
Failed to perform {0} on Storage CS.

Category:
Other

Cause:
Contact Oracle Support Services.

Action:
Contact Oracle Support Services.

ODI-18022
Regeneration failed. User does not have Regenerate privilege.

Category:
Other

Cause:
User does not have regenerate privilege

Action:
Please grant regenerate privilege.

ODI-20001
ODI-20001: Cannot check the key because the Datastore does not exist in the database.

Category:
Other

Cause:
The Datastore referenced by this key did not exist in the database.

Action:
Ensure the Datastore refers to an existing database table.

ODI-20002
ODI-20002: The selected file is not a valid key file.

Category:
Other

Cause:
An invalid encryption key file was selected.

Action:
Select a valid encryption key file.

ODI-20003
ODI-20003: Cannot edit the condition

Category:
Other

Cause:
General Exception invoking editor.

Action:
This is an internal error with no recommended user action.

ODI-20004
ODI-20004: Cannot edit the reference

Category:
Other

Cause:
General Exception invoking editor.

Action:
This is an internal error with no recommended user action.

ODI-20005
ODI-20005: Cannot edit the variable

Category:
Other

Cause:
General Exception invoking editor.

Action:
This is an internal error with no recommended user action.

ODI-20006
ODI-20006: Cannot display table's data. Data is probably already displayed.

Category:
Other

Cause:
General Exception invoking editor.

Action:
This is an internal error with no recommended user action.

ODI-20007
ODI-20007: Cannot display table's data.

Category:
Other

Cause:
General Exception invoking editor.

Action:
This is an internal error with no recommended user action.

ODI-20008
ODI-20008: You cannot Display this Attribute Data. Data is probably already displayed

Category:
Other

Cause:
General Exception invoking editor.

Action:
This is an internal error with no recommended user action.

ODI-20009
ODI-20009: Cannot display data. The datastore resource name is {0} characters long which is longer than allowed by the technology ({1}). Please review the technology settings in Topology.

Category:
Other

Cause:
The datastore resource name exceeded the limit allowed by its technology.

Action:
Ensure the maximum table name length setting in the corresponding technology is correct. Consider changing the datastore resource name to comply.

ODI-20010
ODI-20010: Cannot display this Attribute Data

Category:
Other

Cause:
General Exception invoking editor.

Action:
This is an internal error with no recommended user action.

ODI-20011
ODI-20011: Cannot perform this action: a Column of this Datastore is currently being edited

Category:
Other

Cause:
Another user may be editing this datastore.

Action:
Wait for the other editing session to be committed.

ODI-20012
ODI-20012: Cannot perform this action: the Datastore containing this Column is currently being modified

Category:
Other

Cause:
Another user may be editing this datastore.

Action:
Wait for the other editing session to be committed.

ODI-20013
ODI-20013: Unable to perform the action because the package is currently being modified

Category:
Other

Cause:
Another user may be editing this package.

Action:
Wait for the other editing session to be committed.

ODI-20014
ODI-20014: Cannot encrypt the Procedure: it is currently being modified

Category:
Other

Cause:
Another user may be editing this procedure.

Action:
Wait for the other editing session to be committed.

ODI-20015
ODI-20015: Cannot initialize the Flexfields values

Category:
Other

Cause:
Another user may be editing the flexfield values.

Action:
Wait for the other editing session to be committed.

ODI-20016
ODI-20016: Unable to add project user functions

Category:
Other

Cause:
An unsupported action was attempted.

Action:
No action required as Project user functions are not a valid selection to be added to a label.

ODI-20017
ODI-20017: Unable to add project sequences

Category:
Other

Cause:
An unsupported action was attempted.

Action:
No action required as Project sequences are not a valid selection to be added to a label.

ODI-20018
ODI-20018: Unable to add project variables

Category:
Other

Cause:
An unsupported action was attempted.

Action:
No action required as Project variables are not a valid selection to be added to a label.

ODI-20019
ODI-20019: Unable to get GBO object

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-20020
ODI-20020: Cannot change CKM

Category:
Other

Cause:
Only one CKM is available.

Action:
Import additional CKMs.

ODI-20021
ODI-20021: Cannot change the order of this Command because you do not have 'Edit' privileges on this Object

Category:
Other

Cause:
Insufficient privileges to edit the object.

Action:
Assign additional privileges to edit the object.

ODI-20022
ODI-20022: Could not change the KM

Category:
Other

Cause:
Additional KMs may not be available or installed for the current technology.

Action:
Import additional KMs.

ODI-20024
ODI-20024: Cannot create the cross reference for the condition

Category:
Other

Cause:
Internal error creating cross references for a condition.

Action:
No action required.

ODI-20025
ODI-20025: Cannot create the cross references for the reference

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-20026
ODI-20026: Cannot view this Datastore: one of its Columns is currently being edited

Category:
Other

Cause:
The data store is being edited in another session.

Action:
Wait for the other editing session to end.

ODI-20027
ODI-20027: Cannot view this Column: its Datastore is currently being edited

Category:
Other

Cause:
A package step is being edited in another session.

Action:
Wait for the other session to end.

ODI-20028
ODI-20028: Cannot start execution.

Category:
Other

Cause:
Execution cannot be started due to an internal error.

Action:
No required action.

ODI-20029
ODI-20029: Cannot move a line

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-20030
ODI-20030: Cannot start the generation. The file is probably already open.

Category:
Other

Cause:
Attempt to open report file for output failed.

Action:
Ensure the specified file is not currently open and the file permissions allow for write access before retrying the operation. Consider choosing a different file for output.

ODI-20031
ODI-20031: Cannot Delete a Command being Edited.

Category:
Other

Cause:
An attempt was made to delete a command being edited.

Action:
Save the edit before deleting.

ODI-20032
ODI-20032: Cannot Delete a Command

Category:
Other

Cause:
Internal error.

Action:
No required action

ODI-20033
ODI-20033: Cannot find the KM description

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-20034
ODI-20034: Cannot find the Options list for a Command

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-20035
ODI-20035: Could not find a description for the KM

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-20036
ODI-20036: Impossible to find the technology name, please check your privileges.

Category:
Other

Cause:
The ODI security permissions were insufficient to allow access to the specified technology.

Action:
Ensure the ODI user security permissions are correct.

ODI-20037
ODI-20037: Cannot find data transferred by the Drag'n'Drop

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-20038
ODI-20038: Could not connect

Category:
Other

Cause:
A connection was not established to the selected Logical Schema.

Action:
Ensure the connection data for the Physical Schema of the selected Logical Schema is valid.

ODI-20039
ODI-20039: Incorrect context

Category:
Other

Cause:
A context was not chosen for execution.

Action:
Select an execution context.

ODI-20040
ODI-20040: Problem encountered when determining the context

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-20041
ODI-20041: No candidate datastore was found. Please create a mapping which loads data into this datastore.

Category:
Other

Cause:
There were no datastores in the current model usable as candidates for generating OUT mappings.

Action:
Consider creating an mapping to load data into a datastore of the current model.

ODI-20042
ODI-20042: Property key is empty

Category:
Other

Cause:
The Property key for one of the specified Data Server's properties was not specified.

Action:
Ensure a non-empty key value is supplied or remove the property with this key.

ODI-20043
ODI-20043: Invalid property key entered. Property key maximum length is 250 characters

Category:
Other

Cause:
The Property key for one of the specified Data Server's properties had a length greater than 250 characters.

Action:
Ensure a key value with the valid length is supplied or remove the property with this key.

ODI-20044
ODI-20044: Invalid property value entered. Property value maximum length is 250 characters

Category:
Other

Cause:
The Property value for one of this Data Server's properties had a length greater than 250 characters.

Action:
Ensure a value with the valid length is supplied or remove the property with this value.

ODI-20046
ODI-20046: Unable to change an open object

Category:
Other

Cause:
An object is already open in another editor and cannot be modified.

Action:
Close any other editors which may be locking the object.

ODI-20047
ODI-20047: Unable to change Value

Category:
Other

Cause:
Internal error.

Action:
Review the error details for further information.

ODI-20048
ODI-20048: Invalid Value entered. Value maximum length is 250 characters

Category:
Other

Cause:
The Value for one of this object's Flexfields had a length greater than 250 characters.

Action:
Ensure the value supplied has a valid length.

ODI-20049
ODI-20049: You cannot copy a folder into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Folders cannot be copied into hierarchy of another projects.

ODI-20050
ODI-20050: You cannot copy a knowledge module into another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Knowledge modules cannot be copied into hierarchy of another projects.

ODI-20051
ODI-20051: You cannot copy a package into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Packages cannot be copied into hierarchy of another projects.

ODI-20052
ODI-20052: You cannot copy an interface into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Interfaces cannot be copied into hierarchy of another projects.

ODI-20053
ODI-20053: You cannot copy a procedure into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Procedures cannot be copied into hierarchy of another projects.

ODI-20054
ODI-20054: You cannot move a folder into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Folders cannot be moved into hierarchy of another projects.

ODI-20055
ODI-20055: You cannot move a knowledge module into another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Knowledge modules cannot be moved into hierarchy of another projects.

ODI-20056
ODI-20056: You cannot move a package into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Packages cannot be moved into hierarchy of another projects.

ODI-20057
ODI-20057: You cannot move an interface into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Interfaces cannot be moved into hierarchy of another projects.

ODI-20058
ODI-20058: You cannot move a procedure into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Procedures cannot be moved into hierarchy of another projects.

ODI-20059
ODI-20059: You cannot copy a knowledge module into a package belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Knowledge modules cannot be copied into packages from another projects.

ODI-20060
ODI-20060: You cannot copy an interface into a package belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Interfaces cannot be copied into packages from another projects.

ODI-20061
ODI-20061: You cannot copy a procedure into a package belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Procedures cannot be copied into packages from another projects.

ODI-20062
ODI-20062: You cannot move a knowledge module into a package belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Knowledge modules cannot be moved into packages from another projects.

ODI-20063
ODI-20063: You cannot move an interface into a package belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Interfaces cannot be moved into packages from another projects.

ODI-20064
ODI-20064: You cannot move a step into a package belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Package steps cannot be moved into packages from another projects.

ODI-20065
ODI-20065: You cannot move a procedure into a package belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Procedures cannot be moved into packages from another projects.

ODI-20066
ODI-20066: You cannot copy a folder into another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Folders cannot be copied into hierarchy of another projects.

ODI-20067
ODI-20067: You cannot copy a procedure into another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Procedures cannot be copied into hierarchy of another projects.

ODI-20068
ODI-20068: You cannot copy a variable into another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Variables cannot be copied into hierarchy of another projects.

ODI-20069
ODI-20069: You cannot move a folder into another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Folders cannot be moved into hierarchy of another projects.

ODI-20070
ODI-20070: You cannot move a sequence into another project. Copy the sequence instead.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Sequences cannot be moved into hierarchy of another projects.

ODI-20071
ODI-20071: You cannot move a procedure into another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Procedures cannot be moved into hierarchy of another projects.

ODI-20072
ODI-20072: You cannot move a variable into another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Variables cannot be moved into hierarchy of another projects.

ODI-20073
ODI-20073: You cannot copy a schedule into a scenario belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Schedules cannot be copied into hierarchy of another projects.

ODI-20074
ODI-20074: You cannot move a schedule into a scenario belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Schedules cannot be moved into hierarchy of another projects.

ODI-20075
ODI-20075: You cannot move a folder into one of its subfolders.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Folders cannot be moved into their subfolders.

ODI-20076
ODI-20076: You cannot copy a knowledge module into a package step belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Knowledge modules cannot be copied into package steps from another projects.

ODI-20077
ODI-20077: You cannot copy an interface into a package step belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Interfaces cannot be copied into package steps from another projects.

ODI-20078
ODI-20078: You cannot copy a procedure into a package step belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Procedures cannot be copied into package steps from another projects.

ODI-20079
ODI-20079: You cannot move a knowledge module into a package step belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Knowledge modules cannot be moved into package steps from another projects.

ODI-20080
ODI-20080: You cannot move an interface into a package step belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Interfaces cannot be moved into package steps from another projects.

ODI-20081
ODI-20081: You cannot move a step into a package step belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Steps cannot be moved into package steps from another projects.

ODI-20082
ODI-20082: You cannot move a procedure into a package step belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Procedures cannot be moved into package steps from another projects.

ODI-20083
ODI-20083: Unable to perform the operation. {0} is being edited.

Category:
Other

Cause:
An object is being edited, preventing other operations.

Action:
Save or cancel editing of the object.

ODI-20084
ODI-20084: Only variables from the same project can be placed in a package.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Variables from another projects cannot be placed in packages.

ODI-20085
ODI-20085: Only mappings from the same project can be placed in a package.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Mappings from another project cannot be placed in packages.

ODI-20086
ODI-20086: Only procedures from the same project can be placed in a package.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Procedures from another projects cannot be placed in packages.

ODI-20087
ODI-20087: Error while duplicating

Category:
Other

Cause:
Internal error.

Action:
Review the error details for further information.

ODI-20088
ODI-20088: Error while generating the scenario

Category:
Other

Cause:
Internal error.

Action:
Review the error details for further information.

ODI-20089
ODI-20089: Error during parameter initialization

Category:
Other

Cause:
Internal error.

Action:
Review the error details for further information.

ODI-20090
ODI-20090: Error while duplicating

Category:
Other

Cause:
Internal error.

Action:
Review the error details for further information.

ODI-20091
ODI-20091: An unexpected error occurred.

Category:
Other

Cause:
Internal error.

Action:
Review the error details for further information.

ODI-20092
ODI-20092: An error occurred while replacing the version.

Category:
Other

Cause:
Internal error.

Action:
Review the error details for further information.

ODI-20093
ODI-20093: Scenario generation is not allowed for non-saved object

Category:
Other

Cause:
Scenario generation could not be performed because the source object was not saved.

Action:
Ensure the source object is saved before attempting scenario generation for it.

ODI-20094
ODI-20094: Specify the object name to generate Scenario

Category:
Other

Cause:
Scenario generation could not be performed because the source object's name was not specified.

Action:
Ensure the source object's name is specified before attempting scenario generation for it.

ODI-20095
ODI-20095: Marker Group save was cancelled

Category:
Other

Cause:
Marker group save was cancelled by a user.

Action:
No action required.

ODI-20096
ODI-20096: Unable to edit the action line.

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-20097
ODI-20097: The line Name is mandatory

Category:
Other

Cause:
A value for the Action Line Name field was not specified.

Action:
Enter a non-empty value for the Action Line Name field.

ODI-20098
ODI-20098: Some Datatype Conversions between current and new Technologies are absent

Category:
Other

Cause:
Changing the selected Model's Technology failed because the Physical Architecture did not provide datatype conversion rules for datatypes used by attributes of datastores belonging to the selected model.

Action:
Ensure datatype conversion rules exist for all datatypes used by attributes of datastores belonging to the selected model or do not use datatypes that cannot be converted.

ODI-20099
ODI-20099: Unable to create execution window

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-20100
ODI-20100: Unable to access a join or a filter

Category:
Other

Cause:
Access to a join or filter failed due to insufficient ODI security permissions.

Action:
Ensure the ODI user security permissions are correct for the join or filter object.

ODI-20101
ODI-20101: Unable to find mapping alias

Category:
Other

Cause:
Access to the target mapping failed due to insufficient ODI security permissions.

Action:
Ensure the ODI user security permissions are correct for the target mapping.

ODI-20102
ODI-20102: Unable to find source table alias

Category:
Other

Cause:
Access to the source table failed due to insufficient ODI security permissions.

Action:
Ensure the ODI user security permissions are correct for the source table.

ODI-20103
ODI-20103: Unable to access a target column

Category:
Other

Cause:
Access to the target column failed due to insufficient ODI security permissions.

Action:
Ensure the ODI user security permissions are correct for the target column.

ODI-20105
ODI-20105: "Schema", "Table", "Column" and "Filter" are mandatory fields.

Category:
Other

Cause:
Values for the mandatory "Schema", "Table", "Column" and "Filter" fields were not supplied.

Action:
Ensure values are supplied for these mandatory fields.

ODI-20106
ODI-20106: Schema and Native sequence name are mandatory fields

Category:
Other

Cause:
Values for the mandatory Schema and Native sequence name fields were not supplied.

Action:
Ensure values are supplied for these mandatory fields.

ODI-20107
ODI-20107: A project sequence with the name "{0}" already exists in the project "{1}"

Category:
Other

Cause:
Saving the project sequence failed because the Sequence name was not unique within the Project.

Action:
Ensure the sequence name entered is unique.

ODI-20108
ODI-20108: A global sequence with the name "{0}" already exists

Category:
Other

Cause:
Saving the Global sequence failed because the Global Sequence name was not unique.

Action:
Ensure the sequence name entered is unique.

ODI-20109
ODI-20109: Error while restoring the version

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-20110
ODI-20110: No version of this element exist.

Category:
Other

Cause:
The selected version of this object was not found in version repository.

Action:
Create or restore the selected version of the object.

ODI-20111
ODI-20111: Sub-model code cannot be empty.

Category:
Other

Cause:
A value of the mandatory Sub-model code field was not supplied.

Action:
Enter a non-empty value for the Sub-model code field.

ODI-20112
ODI-20112: The path defined in the logical schema is incorrect.

Category:
Other

Cause:
Incorrect path was specified in physical schema which is linked to the logical schema of this datastore in the current context.

Action:
Ensure the path specified in physical schema is correct.

ODI-20113
ODI-20113: The GUID that was supplied does not match the GUID for this user in the external identity store. Please retrieve the correct GUID before saving.

Category:
Other

Cause:
The supplied GUID did not match GUID from external identity store.

Action:
Provide a valid GUID.

ODI-20114
ODI-20114: Error while subscribing

Category:
Other

Cause:
An unexpected error occurred while trying to subscribe a datastore for CDC.

Action:
Review the error details for further information.

ODI-20115
ODI-20115: Error while stopping journalizing

Category:
Other

Cause:
An unexpected error occurred while trying to stop journalizing.

Action:
Review the error details for further information.

ODI-20116
ODI-20116: Aliases are specified and are not unique.

Category:
Other

Cause:
Duplicate Alises were detected.

Action:
Change the name of the join key alias.

ODI-20117
ODI-20117: Error while executing command line.

Category:
Other

Cause:
An unexpected error occurred while trying to open the Report.

Action:
Review the error details for further information.

ODI-20118
ODI-20118: Error while building the menu.

Category:
Other

Cause:
An unexpected error occurred while building a menu.

Action:
Review the error details for further information.

ODI-20119
ODI-20119: Error during generation.

Category:
Other

Cause:
An unexpected error occurred during the report generation.

Action:
Review the error details for further information.

ODI-20120
ODI-20120: Error while journalizing

Category:
Other

Cause:
An unexpected error occurred during journalizing.

Action:
Review the error details for further information.

ODI-20121
ODI-20121: Error while saving the diagram

Category:
Other

Cause:
An unexpected error occurred during the saving the diagram.

Action:
Review the error details for further information.

ODI-20122
ODI-20122: Error while unsubscribing

Category:
Other

Cause:
An unexpected error occurred during the unsubscribing action.

Action:
Review the error details for further information.

ODI-20123
ODI-20123: Error while executing query

Category:
Other

Cause:
An unexpected error occurred during query execution.

Action:
Check the error details for further actions.

ODI-20124
ODI-20124: Operation cancelled by user.

Category:
Other

Cause:
Operation cancelled by user

Action:
Review the other messages for further actions.

ODI-20126
ODI-20126: TreeTableColumn cannot be added

Category:
Other

Cause:
TreeTableColumn with this order number already exists

Action:
Contact Oracle Support Services.

ODI-20127
ODI-20127: This TreeTableColumn cannot be removed.

Category:
Other

Cause:
TreeTableColumn does not exist.

Action:
Contact Oracle Support Services.

ODI-20128
ODI-20128: Could not rollback.

Category:
Other

Cause:
An error occurred during rollback operation.

Action:
Review other messages for further information.

ODI-20129
ODI-20129: Exception occurred.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Review the error details for further information.

ODI-20130
ODI-20130: You must select a folder.

Category:
Other

Cause:
A folder was not selected.

Action:
Select a folder before attempting this action.

ODI-20131
ODI-20131: Cannot retrieve the table list

Category:
Other

Cause:
An error occured while trying to retrieve a list of tables.

Action:
Review the message log for more information. If problem persists contact Oracle Support Services.

ODI-20132
ODI-20132: An interface cannot be moved to another project

Category:
Other

Cause:
An unsupported drag and drop operation was attempted.

Action:
No action required.

ODI-20133
ODI-20133: A procedure cannot be moved to another project

Category:
Other

Cause:
An unsupported drag and drop operation was attempted.

Action:
No action required.

ODI-20134
ODI-20134: A variable cannot be moved to another project

Category:
Other

Cause:
An unsupported drag and drop operation was attempted.

Action:
No action required

ODI-20135
ODI-20135: A step cannot be moved to another package

Category:
Other

Cause:
An unsupported drag and drop operation was attempted.

Action:
No action required

ODI-20138
ODI-20138: An error occured during: dragGesture

Category:
Other

Cause:
An unexpected error occurred while dragging an object.

Action:
Review the message log for more information. If problem persists contact Oracle Support Services.

ODI-20139
ODI-20139: An error occured during: dragEnter

Category:
Other

Cause:
An unexpected error occurred during a drag operation.

Action:
Review the error details for further information.

ODI-20140
ODI-20140: An error occured during: Drop

Category:
Other

Cause:
An unexpected error occurred while dropping an object.

Action:
Review the message log for more information. If problem persists contact Oracle Support Services.

ODI-20141
ODI-20141: Login Creation Error

Category:
Other

Cause:
An unexpected error occurred while creating a new Login.

Action:
Review the error details for further information.

ODI-20142
ODI-20142: Popup Menu Creation Error

Category:
Other

Cause:
An unexpected error occurred while creating a popup menu.

Action:
Review the error details for further information.

ODI-20144
ODI-20144: Error while Deleting

Category:
Other

Cause:
An unexpected error occurred while deleting a tree object.

Action:
Review the error details for further information.

ODI-20145
ODI-20145: Error while Opening splitframe.

Category:
Other

Cause:
An unexpected error occurred opening a frame.

Action:
Review the error details for further information.

ODI-20146
ODI-20146: Error occured during duplication

Category:
Other

Cause:
An unexpected error occurred while duplicating an object.

Action:
Review the error details and message log for more information.

ODI-20148
ODI-20148: An error occured during: drag over the object

Category:
Other

Cause:
An unexpected error occurred while dragging an object over another object.

Action:
Review the error details and message log for more information.

ODI-20149
ODI-20149: Logical schema can't be undefined

Category:
Other

Cause:
A Logical schema was not defined.

Action:
Define a Logical schema.

ODI-20150
ODI-20150: KM or Procedure already encrypted. No encryption was performed.

Category:
Other

Cause:
The requested object has already been encrypted.

Action:
No action required.

ODI-20151
ODI-20151: File is not found. Invalid file location

Category:
Other

Cause:
The specified file could not be located in the file system.

Action:
Ensure file location specified is valid and accessible.

ODI-20152
ODI-20152: Object cannot be deleted

Category:
Other

Cause:
The specified object could not be deleted.

Action:
Ensure the specified object exists and the security permissions permit deletion.

ODI-20153
ODI-20153: The following field is missing: Syntax

Category:
Other

Cause:
User function syntax has not been specified.

Action:
Specify the function syntax.

ODI-20155
ODI-20155: Changing the Logical Schema may require a re-generation of your Mappings. It may be better to modify the Topology information instead.

Category:
Other

Cause:

Action:

ODI-20158
ODI-20158: Datastores distribution failed.

Category:
Other

Cause:
An error occured during the datastore distribution process.

Action:
Review the message details and message log for more information. If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

ODI-20159
ODI-20159: The Attribute {0} is used as a Reference

Category:
Other

Cause:
An attempt was made to delete an attribute referenced by another object.

Action:
Delete the object which references this attribute then retry deleting this attribute.

ODI-20160
ODI-20160: The table {0} does not exist.

Category:
Other

Cause:
An error occured while executing the SQL request

Action:
Review the message details for more information. If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

ODI-20161
ODI-20161: Standard reverse-engineering failed.

Category:
Other

Cause:
An error occured during the standard reverse-engineering process.

Action:
Ensure the technology or driver supports standard reverse-engineering. Otherwise choose Customized Reverse and select an appropriate RKM for the technology.

ODI-20162
ODI-20162: The context is not valid.

Category:
Other

Cause:
A Context was not specified.

Action:
Specify a Context.

ODI-20163
ODI-20163: Unable to add object

Category:
Other

Cause:
An error occurred while dragging and dropping an object.

Action:
Review the message details and message log for more information.

ODI-20164
ODI-20164: The line Name is mandatory

Category:
Other

Cause:
A name was not specified.

Action:
Specify a Line name.

ODI-20165
ODI-20165: The project name {0} is a reserved word.

Category:
Other

Cause:
A reserved word was used as the name of a project.

Action:
Enter a different project name.

ODI-20166
ODI-20166: The project code {0} is a reserved word.

Category:
Other

Cause:
A reserved word was used as the project code.

Action:
Enter a different project code.

ODI-20167
ODI-20167: Logical schema is not set for the current context

Category:
Other

Cause:
A Logical schema was not set for the current context.

Action:
Ensure the Logical Schema is not set to "Undefined" in the Context editor.

ODI-20168
ODI-20168: Logical schema is not set for the current context

Category:
Other

Cause:
A Logical schema was not set for the current context.

Action:
Ensure the Logical Schema is not set to "Undefined" in the Context editor.

ODI-20169
ODI-20169: The field {0} is mandatory.

Category:
Other

Cause:
A mandatory field was not specified.

Action:
Enter a value for this field.

ODI-20170
ODI-20170: You are trying to insert this versioned object but the version was deleted. Please re-create a version for this object.

Category:
Other

Cause:
The requested version of the object did not exist in the repository.

Action:
Recreate the required version of this object.

ODI-20171
ODI-20171: The label already contains a child of {0}. To add {1} to the label, you should delete {2} {3}. It is advised to use the button "synchronize" later to check the label's coherence.

Category:
Other

Cause:
The label already contained the specified object as a child.

Action:
Delete the child object from the label before retrying the addition. Consider using the synchronize option to verify the label's coherence.

ODI-20172
ODI-20172: The label already contains a parent of {0}. To add {1} to the label, you should delete {2} {3}. It is advised to use the button "synchronize" later to check the label's coherence.

Category:
Other

Cause:
The label has already contained the specified object as a parent of {0}.

Action:
Delete the parent object from the label before retrying the addition. Consider using the synchronize option to verify the label's coherence.

ODI-20173
ODI-20173: An error occurred while generating the procedure

Category:
Other

Cause:
An unexpected error occurred while generating a procedure.

Action:
Review the error details for further information.

ODI-20174
ODI-20174: Folder {0} already contains an mapping named {1}

Category:
Other

Cause:
An mapping of the same name already existed in the specified folder.

Action:
Specify another name for the mapping.

ODI-20175
ODI-20175: You cannot give an empty name to an mapping

Category:
Other

Cause:
The Mapping's name was not specified.

Action:
Enter a non-empty value for the mapping's name.

ODI-20176
ODI-20176: You cannot create multiple mappings with the same name

Category:
Other

Cause:
An mapping of the same name already existed.

Action:
Specify a different name for the mapping.

ODI-20177
ODI-20177: You must select a generation folder

Category:
Other

Cause:
The Generation folder was not selected.

Action:
Select a generation folder.

ODI-20180
ODI-20180: You cannot choose an expiration date in the past.

Category:
Other

Cause:
Entered expiration date was in the past.

Action:
Enter valid expiration date.

ODI-20181
ODI-20181: You cannot set an expiration date if there is no password.

Category:
Other

Cause:
No password was entered.

Action:
Enter a password before setting an expiration date.

ODI-20182
ODI-20182: Error while opening window

Category:
Other

Cause:
An unexpected error occurred while opening a window.

Action:
Review the error details for further information.

ODI-20183
ODI-20183: Error while refreshing Label

Category:
Other

Cause:
An unexpected error occurred while refreshing a label.

Action:
Review the error details for further information.

ODI-20184
ODI-20184: The request to retrieve the sequence list has not been defined on the technology.

Category:
Other

Cause:
The query for retrieving sequences has not been defined for the technology.

Action:
Update the technology with the sequence query syntax.

ODI-20185
ODI-20185: Error while opening window

Category:
Other

Cause:
An unexpected error occurred while opening a window.

Action:
Review the error details for further information.

ODI-20186
ODI-20186: Error while saving

Category:
Other

Cause:
An unexpected error occurred while saving an object.

Action:
Review the error details for further information.

ODI-20187
ODI-20187: Error while adding the marker

Category:
Other

Cause:
An unexpected error occurred while adding a marker.

Action:
Review the error details for further information.

ODI-20188
ODI-20188: This object is locked by another user. You cannot edit its markers.

Category:
Other

Cause:
The object was locked by another user.

Action:
Wait until the object is unlocked. Consider contacting the user who has the object locked.

ODI-20189
ODI-20189: You do not have the sufficient privileges to reverse-engineer a model

Category:
Other

Cause:
The model could not be reverse-engineered due to insufficient privileges.

Action:
Ensure the SUPERVISOR or owner of model grants the appropriate permissions.

ODI-20190
ODI-20190: You cannot reverse engineer a model in 'Standard' mode: the model technology assumes RKM to be selected.

Category:
Other

Cause:
No RKM was specified for this model.

Action:
Select an RKM for this model.

ODI-20191
ODI-20191: The model you want to reverse-engineer references a logical schema that no longer exists.

Category:
Other

Cause:
The referenced Logical Schema for the Model was not found.

Action:
Ensure a valid Logical Schema is assigned for the Model.

ODI-20192
ODI-20192: Error while replacing versioned object

Category:
Other

Cause:
An unexpected error occurred while replacing a versioned object.

Action:
Review the error details for further information.

ODI-20193
ODI-20193: An error occurred during the versioning operation.

Category:
Other

Cause:
An unexpected error occurred during versioning.

Action:
Review the error details for further information.

ODI-20194
ODI-20194: Your license does not allow Versioning operations.

Category:
Other

Cause:
The license does not include versioning.

Action:
Upgrade the license.

ODI-20195
ODI-20195: Unable to unlock this object

Category:
Other

Cause:
An unexpected error occurred while unlocking an object.

Action:
Review the error details for further information.

ODI-20196
ODI-20196: You must select an object version

Category:
Other

Cause:
No version selected for checkout.

Action:
Select version for checkout.

ODI-20197
ODI-20197: Your license does not allow Versioning operations.

Category:
Other

Cause:
The current license does not inlude versioning.

Action:
Upgrade the license to include versioning.

ODI-20198
ODI-20198: Error while creating the version.

Category:
Other

Cause:
An unexpected error occurred while creating a version.

Action:
Review the error details for further information.

ODI-20199
ODI-20199: Your license does not allow Versioning operations.

Category:
Other

Cause:
The license does not include versioning.

Action:
Upgrade your license.

ODI-20200
ODI-20200: An error happened while comparing the versions

Category:
Other

Cause:
An unexpected error occurred while comparing versions.

Action:
Review the error details for further information.

ODI-20201
ODI-20201: Error while refreshing.

Category:
Other

Cause:
An unexpected error occurred while refreshing.

Action:
Review the error details for further information.

ODI-20202
ODI-20202: Synchronisation was stopped by the user.

Category:
Other

Cause:
Synchronization was stopped by the user.

Action:
No action is required.

ODI-20203
ODI-20203: The current version for this object no longer exists. Please create a new version for this object.

Category:
Other

Cause:
The current version for this object was not found in the repository.

Action:
Create a new version for this object.

ODI-20205
ODI-20205: Could not delete object. This object is being used.

Category:
Other

Cause:
The object deletion failed because it was already in use.

Action:
Remove the usage of the selected object before retrying the deletion.

ODI-20206
ODI-20206: Could not delete object. This object is being displayed.

Category:
Other

Cause:
The object deletion failed because it was being displayed.

Action:
Close object before retrying the deletion.

ODI-20208
ODI-20208: A code was duplicated:

Category:
Other

Cause:
A Flex field with the same code already existed.

Action:
Enter another Flex field code.

ODI-20209
ODI-20209: An error occurred.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Review the error details for further information.

ODI-20210
ODI-20210: Error When Printing...

Category:
Other

Cause:
An unexpected error occurred while printing.

Action:
Review the error details for further information.

ODI-20211
ODI-20211: Error When Displaying Node...

Category:
Other

Cause:
An unexpected error occurred while displaying a node.

Action:
Review the error details for further information.

ODI-20212
ODI-20212: An error occurred while checking errors

Category:
Other

Cause:
An unexpected error occurred while checking errors.

Action:
Review the error details for further information.

ODI-20213
ODI-20213: An error occurred while recovering an object in a node

Category:
Other

Cause:
An unexpected error occurred while recovering an object in a node.

Action:
Review the error details for further information.

ODI-20214
ODI-20214: An error occurred while deleting

Category:
Other

Cause:
An unexpected error occurred while deleting an object.

Action:
Review the error details for further information.

ODI-20216
ODI-20216: Error while deleting

Category:
Other

Cause:
An unexpected error occurred while deleting an object.

Action:
Review the error details for further information.

ODI-20217
ODI-20217: Error while executing the reverse-engineering

Category:
Other

Cause:
An unexpected error occurred while reverse engineering.

Action:
Review the error details for further information.

ODI-20218
ODI-20218: Error during duplication ...

Category:
Other

Cause:
An unexpected error occurred during duplication.

Action:
Review the error details for further information.

ODI-20219
ODI-20219: Error while opening

Category:
Other

Cause:
An unexpected error occurred while opening an object.

Action:
Review the error details for further information.

ODI-20220
ODI-20220: Error during data loading ....

Category:
Other

Cause:
An unexpected error occurred while loading data.

Action:
Review the error details for further information.

ODI-20221
ODI-20221: Error during execution ...

Category:
Other

Cause:
An unexpected error occurred during execution.

Action:
Review the error details for further information.

ODI-20222
ODI-20222: Error during scenario creation ...

Category:
Other

Cause:
An unexpected error occurred during scenario generation.

Action:
Review the error details for further information.

ODI-20223
ODI-20223: Error When Purging Log

Category:
Other

Cause:
An unexpected error occurred while purging the log.

Action:
Review the error details for further information.

ODI-20224
ODI-20224: An interface with the same name already exists in this folder. Please change the name of the new interface.

Category:
Other

Cause:
An interface with the same name already existed in this folder.

Action:
Specify another name for the interface.

ODI-20225
ODI-20225: Error while creating the popup menu

Category:
Other

Cause:
An unexpected error occurred while creating a popup menu.

Action:
Review the error details for further information.

ODI-20226
ODI-20226: Error while applying the changes

Category:
Other

Cause:
An unexpected error occurred while saving changes.

Action:
Review the error details for further information.

ODI-20227
ODI-20227: You cannot copy this attribute. Attribute name already in use.

Category:
Other

Cause:
Attribute copy failed because the Datastore already contained an attribute with the same name.

Action:
Select another attribute to drop to datastore.

ODI-20228
ODI-20228: Error while creating the popup menu

Category:
Other

Cause:
Retrieval of the Available Methods for the column failed.

Action:
Ensure the repository database connection is not broken and the ODI Security permissions are correct.

ODI-20229
ODI-20229: Unable to create condition.

Category:
Other

Cause:
The editor for the Condition could not be opened.

Action:
Ensure the repository database connection is not broken and the ODI Security permissions are correct.

ODI-20230
ODI-20230: Error while creating the popup menu

Category:
Other

Cause:
Retrieval of the Available Methods for the Condition failed.

Action:
Ensure the repository database connection is not broken and the ODI Security permissions are correct.

ODI-20231
ODI-20231: Unable to create a synonym for this table.

Category:
Other

Cause:
An unexpected error occurred while creating a synonym.

Action:
Review the error details for further information.

ODI-20232
ODI-20232: Error while deleting attributes

Category:
Other

Cause:
An unexpected error occurred while deleting attributes.

Action:
Review the error details for further information.

ODI-20233
ODI-20233: Error during the drag-and-drop operation

Category:
Other

Cause:
An unexpected error occurred during a drag and drop operation.

Action:
Review the error details for further information.

ODI-20234
ODI-20234: You do not have the sufficient privileges to add this object.

Category:
Other

Cause:
The operation failed due to insufficient ODI security on Attribute.

Action:
Ensure the ODI user security permissions are correct specifically the Attribute Duplication setting.

ODI-20235
ODI-20235: Error during the drag-and-drop operation

Category:
Other

Cause:
An unexpected error occurred during a drag and drop operation

Action:
Review the error details for further information.

ODI-20236
ODI-20236: You do not have the sufficient privileges to add this object.

Category:
Other

Cause:
The operation failed due to insufficient ODI security on Datastore.

Action:
Ensure the ODI user security permissions are correct.

ODI-20237
ODI-20237: Unable to duplicate the attribute.

Category:
Other

Cause:
An unexpected error occurred while duplicating an attribute.

Action:
Review the error details for further information. Ensure that the repository connection is still valid.

ODI-20238
ODI-20238: Unable to duplicate the table.

Category:
Other

Cause:
An unexpected error occurred while duplicating a table.

Action:
Review the error details for further information. Ensure that the repository connection is still valid.

ODI-20239
Error during the action

Category:
Other

Cause:
An unexpected error occurred during a user action.

Action:
Review the error details for further information.

ODI-20240
ODI-20240: Error while deleting

Category:
Other

Cause:
An unexpected error occurred during a delete operation.

Action:
Review the error details for further information. Ensure that the repository connection is valid.

ODI-20241
ODI-20241: Unable to apply changes.

Category:
Other

Cause:
The changes to the filter could not be applied.

Action:
Save the object before retrying to apply the filter.

ODI-20242
ODI-20242: Error while creating the popup menu

Category:
Other

Cause:
Retrieval of the Available Methods for the filter failed.

Action:
Ensure the repository database connection is not broken and the ODI Security permissions are correct.

ODI-20243
ODI-20243: Unable to add an attribute.

Category:
Other

Cause:
An unexpected error occurred while adding an attribute.

Action:
Review the error details for further information. Ensure that the repository connection is open.

ODI-20244
ODI-20244: Unable to add reference

Category:
Other

Cause:
An unexpected error occurred while adding a reference.

Action:
Review the error details for further information. Ensure that the repository connection is open.

ODI-20245
ODI-20245: Unable to add table

Category:
Other

Cause:
An unexpected error occurred while adding a table.

Action:
Review the error details for further information. Ensure that the repository connection is open.

ODI-20246
ODI-20246: Error while applying the changes

Category:
Other

Cause:
The reference to the Model could not be created.

Action:
Ensure the repository database connection is not broken and the ODI Security permissions are correct.

ODI-20247
ODI-20247: Unable to add key.

Category:
Other

Cause:
An unexpected error occurred while adding a key.

Action:
Review the error details for further information.

ODI-20248
ODI-20248: Error while opening window

Category:
Other

Cause:
The editor could not be opened.

Action:
Save the object before retrying the edit.

ODI-20249
ODI-20249: Error while creating the popup menu

Category:
Other

Cause:
An unexpected error occurred while creating a popup menu.

Action:
Review the error details for further information.

ODI-20250
ODI-20250: Error while

Category:
Other

Cause:
Internal error.

Action:
Review the error details for further information.

ODI-20251
ODI-20251: An unexpected error has occurred

Category:
Other

Cause:
Unable to acess the Security Authorization settings.

Action:
Ensure the repository database connection is not broken and the ODI Security permissions are correct.

ODI-20252
ODI-20252: Unable to apply changes.

Category:
Other

Cause:
Saving the model condition failed.

Action:
Ensure the repository database connection is not broken and the ODI Security permissions are correct.

ODI-20253
ODI-20253: The object was deleted by another user

Category:
Other

Cause:
The operation could not be performed because the specified object could not found.

Action:
Refresh the view and retry the operation.

ODI-20254
ODI-20254: The marker was deleted by another user

Category:
Other

Cause:
The operation could not be performed because the specified Marker object was in an Inconsistent state.

Action:
Refresh the view and retry the operation.

ODI-20255
ODI-20255: Marker name is mandatory

Category:
Other

Cause:
Marker could not be saved because the mandatory Name field was not entered.

Action:
Enter a value in the Marker name field.

ODI-20256
ODI-20256: You do not have the sufficient privileges to change the marker

Category:
Other

Cause:
Modification of the Marker failed due to insufficient ODI security privileges.

Action:
Ensure the ODI user security permissions are correct.

ODI-20257
ODI-20257: The Where text is mandatory when the Filter is active for a static control.

Category:
Other

Cause:
The WHERE clause was null or empty.

Action:
Ensure the WHERE clause is valid.

ODI-20258
ODI-20258: It is not possible to check the expression due to DBMS connection failure

Category:
Other

Cause:
Connection to the DBMS failed.

Action:
Ensure the DBMS is available and the connection information to it is correctly specified.

ODI-20259
ODI-20259: cannot show the data since the join points to different connections

Category:
Other

Cause:
Unable to retrieve data due to a conflict between the physical schemas involved.

Action:
Ensure the Topology or Context settings are correct and multiple data stores in the same Source Set are not connected using different Physical Schemas.

ODI-20260
ODI-20260: Name and Code columns of the FlexField cannot be empty.

Category:
Other

Cause:
FlexField name or code were found to be empty or null.

Action:
Enter a name and a code for the FlexField.

ODI-20261
ODI-20261: The "Procedure Name" is mandatory.

Category:
Other

Cause:
The "Procedure Name" field value was not specified.

Action:
Enter a value for the "Procedure Name" field.

ODI-20262
ODI-20262: Logical Schema is not selected.

Category:
Other

Cause:
There is no Logical Schema selected for this variable.

Action:
Select a Logical Schema.

ODI-20263
ODI-20263: Please enter the duration in a format such as 5s (seconds), 10m (minutes), 1d (days), 1y (years).

Category:
Other

Cause:
Duration is specified in an invalid format

Action:
Please change duration such that it comprises an integer followed by a time indicator, for example 10s, 30d, 1y

ODI-20300
ODI-20300: Error while printing the diagram

Category:
Other

Cause:
An unexpected condition has occurred in the print system.

Action:
Check the printer settings and physical printer.

ODI-20301
ODI-20301: Error while saving the diagram

Category:
Other

Cause:
The save file could not be created.

Action:
Check the destination folder is writable and that their is sufficient disk space.

ODI-20310
Unsupported Flavor

Category:
Other

Cause:
An attempt was made to drag and drop an object into an unsupported area of the canvas.

Action:
Drag a different object type or drop the object into a valid area.

ODI-20311
ODI-20311: An unexpected exception occurred while reading or writing a text in a business object.

Category:
Other

Cause:
An unexpected exception occurred while reading or writing text.

Action:
Review the console output or logs for additional information.

ODI-20312
ODI-20312: An error occurred while printing.

Category:
Other

Cause:
An error occurred while printing.

Action:
Ensure that the printer is configured properly.

ODI-20313
ODI-20313: Could not double click

Category:
Other

Cause:
An unexpected error has occured.

Action:
Contact Oracle Support Services.

ODI-20315
ODI-20315: Invalid Password

Category:
Other

Cause:
The Password is incorrect.

Action:
Correct the password and try again.

ODI-20316
ODI-20316: A timeout occurred while trying to establish a connection.

Category:
Other

Cause:
A timeout error occurred while connecting to the database.

Action:
Verify that the Database Connection details are correct and the database is available.

ODI-20317
ODI-20317: The field "{0}" is mandatory.

Category:
Other

Cause:
A value has not been provided for a required field.

Action:
Enter a value for the named field.

ODI-20318
ODI-20318: The icon {0} cannot be found.

Category:
Other

Cause:
An unexpected error has occured.

Action:
Contact Oracle Support Services.

ODI-20319
ODI-20319: {0} is not a valid date for field {1}. The format is: {2}

Category:
Other

Cause:
The format of the date does not match the required format.

Action:
Enter a valid date using the correct date format.

ODI-20320
ODI-20320: Error when applying changes.

Category:
Other

Cause:
An unexpected error has occurred.

Action:
Contact Oracle Support Services.

ODI-20321
ODI-20321: Error when initializing the panel.

Category:
Other

Cause:
An unexpected error has occurred.

Action:
Contact Oracle Support Services.

ODI-20322
ODI-20322: Unable to add a Step.

Category:
Other

Cause:
An unexpected error has occurred.

Action:
Contact Oracle Support Services.

ODI-20323
ODI-20323: Unable to execute the step

Category:
Other

Cause:
An unexpected error has occurred.

Action:
Contact Oracle Support Services.

ODI-20324
ODI-20324: Cannot execute the Package

Category:
Other

Cause:
An unexpected error has occurred.

Action:
Contact Oracle Support Services.

ODI-20325
ODI-20325: Unable to open the linked object.

Category:
Other

Cause:
An unexpected error has occurred.

Action:
Contact Oracle Support Services.

ODI-20326
ODI-20326: Unable to edit the text

Category:
Other

Cause:
An unexpected error has occurred.

Action:
Contact Oracle Support Services.

ODI-20327
ODI-20327: Unable to modify the value.

Category:
Other

Cause:
An unexpected error has occurred.

Action:
Contact Oracle Support Services.

ODI-20328
ODI-20328: Unable to define the next Step.

Category:
Other

Cause:
An unexpected error has occurred.

Action:
Contact Oracle Support Services.

ODI-20329
ODI-20329: Unable to delete Steps(s). You do not have Edit privileges.

Category:
Other

Cause:
An error occurred while attempting to delete one or more package steps.

Action:
Update security settings to allow step editing privileges.

ODI-20330
ODI-20330: Unable to delete Link(s). You do not have Edit privileges.

Category:
Other

Cause:
You must have Edit privilege on each steps of the link.

Action:
Review the Security settings for the steps and ensure that you have the correct permissions.

ODI-20331
ODI-20331: The Step diagram is not be accessible.

Category:
Other

Cause:
You do not have permission to access this step.

Action:
Check the diagram security settings and verify that you have permission to access the diagram.

ODI-20332
ODI-20332: Cannot change the position of this object

Category:
Other

Cause:
An unexpected error has occurred.

Action:
Contact Oracle Support Services.

ODI-20333
ODI-20333: Cannot view this Step because the Package is being edited

Category:
Other

Cause:
A package step cannot be viewed while the parent package is being edited.

Action:
Close the package editor.

ODI-20335
ODI-20335: Printing Options not accessible.

Category:
Other

Cause:
An unexpected error occurred while printing a package.

Action:
Review the log file for additional info about the exception.

ODI-20336
ODI-20336: Unknown event sent to the Package event manager.

Category:
Other

Cause:
An unexpected error has occurred.

Action:
Contact Oracle Support Services.

ODI-20337
ODI-20337: A Knowledge Module cannot be added as a Step.

Category:
Other

Cause:
Only a DataStore,Model,Sub Model,Interface,Procedure or Variable can be added as a Step.

Action:
Use a valid object type for your step creation.

ODI-20338
ODI-20338: A starting Step must be defined.

Category:
Other

Cause:
A Starting step has been defined.

Action:
Select the first step in the package and mark is the starting step.

ODI-20339
ODI-20339: One or more Steps are not linked.

Category:
Other

Cause:
All steps must be linked.

Action:
Ensure that all steps are linked .

ODI-20340
ODI-20340: Only one starting Step can be defined.

Category:
Other

Cause:
A package must have one and only one starting steps.

Action:
Ensure that you have only one starting step defined .

ODI-20341
ODI-20341: You do not have the appropriate privileges to edit a package step.

Category:
Other

Cause:
An attempt was made to edit or view a package step, but the user does not have privileges to access the step.

Action:
Update security settings for the user to allow package and step access.

ODI-20342
ODI-20342: Cannot open the Expression Editor

Category:
Other

Cause:
An unexpected error has occured.

Action:
Contact Oracle Support Services.

ODI-20343
ODI-20343: There are errors in your diagram

Category:
Other

Cause:
The diagram may contain objects that are not connected, or objects that are not completely defined.

Action:
Check the diagram and ensure that all objects are connected and fully defined.

ODI-20344
ODI-20344: Cannot launch the editor for this expression

Category:
Other

Cause:
An error occured while retrieving the language for the expression. This may be due to an unexpected exception, or the language may not be available for the schema's technology.

Action:
Review the message log for additional errors. Ensure that the schema has a valid technology for which the language is set.

ODI-20345
ODI-20345: Cannot change the clause position

Category:
Other

Cause:
An unexpected internal exception has occured.

Action:
Contact Oracle Support Services.

ODI-20346
ODI-20346: Cannot get the boolean value of an option

Category:
Other

Cause:
The boolean value of the option could not be retrieved due to a security error.

Action:
Review the message log and contact Oracle Support Services for further assistance.

ODI-20347
ODI-20347: Error during data transfer for drag and drop

Category:
Other

Cause:
An internal error occured while dropping the object into the diagram.

Action:
Review the message log for additional information and contact Oracle Support Services for further assistance.

ODI-20348
ODI-20348: An interface with the same name already exists in this folder. Please change the name of the new interface.

Category:
Other

Cause:
An interface with the specified name exists in the folder. The interface name must be unique within a folder.

Action:
Enter a new interface name that is unique within the folder.

ODI-20349
ODI-20349: Unknown event detected by the event manager. Please contact Oracle Support Services.

Category:
Other

Cause:
The Package Event Manager was called to action an unknown event.

Action:
Contact Oracle Support Services for further assistance.

ODI-20350
ODI-20350: Your diagram contains one or more FATAL/CRITICAL errors preventing display of the Flow Editor

Category:
Other

Cause:
The diagram is incomplete or contains errors that prevent the Flow Editor being displayed.

Action:
Return to the diagram tab and review the error messages using the errors and warnings button in the toolbar. Fix the errors in order to access the Flow Editor.

ODI-20351
ODI-20351: Error adding source to Quick Edit source table.

Category:
Other

Cause:
An internal error occured which prevented the source being added.

Action:
Contact Oracle Support Services for further assistance.

ODI-20352
ODI-20352: Error adding target datastore to Quick Edit mapping table.

Category:
Other

Cause:
An internal error occured which prevented the target being added.

Action:
Contact Oracle Support Services for further assistance.

ODI-20353
ODI-20353: Only a single column may be pasted into a Quick Edit table.

Category:
Other

Cause:
The clipboard contains multiple columns. Quick Edit only supports pasting a single cell into a table.

Action:
Select the cells to be copied and paste them one at a time.

ODI-20354
ODI-20354: Paste targets must be in the same column as the previous copy. This does not apply to Expression columns (Lookup Expression, Join Expression, Filter Expression, and Mapping Expression).

Category:
Other

Cause:
You have selected a value from one column, and tried to paste it into a different column. This is only supported for Expression Columns.

Action:
Please enter the values into the cell manually.

ODI-20355
ODI-20355: Duplicate value is not supported on this column.

Category:
Other

Cause:
The paste operation is not permitted in the Alias and Target Column Name fields as these fields must contain a unique value.

Action:
Please enter the Alias or Name field manually.

ODI-20356
ODI-20356: Can not perform paste into a read-only column.

Category:
Other

Cause:
The Paste operation is not permitted on read-only columns.

Action:
You may not update this value in the table.

ODI-20357
ODI-20357: Can not perform deletion because the target datastore is not temporary.

Category:
Other

Cause:
An attempt was made to delete a row in the target, but the target datastore is not a temporary table. Only rows in a temporary target table may be deleted.

Action:
You cannot delete the row.

ODI-20358
ODI-20358: Interface cannot be saved because it has a fatal error: {0}.

Category:
Other

Cause:
The Interface could not be saved because it contains a fatal error which must be resolved.

Action:
Review the errors in the Diagram tab and resolve the fatal errors.

ODI-20359
ODI-20359: Only one cell can be copied one at a time.

Category:
Other

Cause:
More than one cell was selected. Quick Edit only supports copying a single cell.

Action:
Select and copy a single cell.

ODI-20360
ODI-20360: Only Expression columns support Copy and Paste from other applications. For all other columns, please perform a copy first on that column before pasting.

Category:
Other

Cause:
Only values from other applications may be copied into Expression columns.

Action:
For all other columns, perform a copy first on that column before pasting.

ODI-20361
ODI-20361: Can not perform Copy and Paste across tables, except for Expression columns (Lookup Expression, Join Expression, Filter Expression, and Mapping Expression).

Category:
Other

Cause:
Values may not be copied between tables in Quick Edit, apart from between Expression columns.

Action:
Please enter the values manually.

ODI-20362
ODI-20362: Couldn't connect to Web Service

Category:
Other

Cause:
An error occured while creating a connection to the Web Service.

Action:
Ensure that the Web Service is accessible and WSDL URL is correct.

ODI-20363
ODI-20363: Error while exporting request

Category:
Other

Cause:
The request could not be exported

Action:
Check that there is sufficient disk space and that the target directory is accessible.

ODI-20364
ODI-20364: Error while parsing the XML file

Category:
Other

Cause:
An error occured while parsing the XML file

Action:
Ensure that the correct XML file is specified and that it is correctly structured

ODI-20365
ODI-20365: There is no port with SOAP binding defined on this service

Category:
Other

Cause:
The referenced service does not support the specified port

Action:
Specify a valid port for the service

ODI-20366
ODI-20366: The timeout must be an integer value.

Category:
Other

Cause:
The value entered for the timeout is not a valid integer

Action:
Enter a valid integer value

ODI-20367
ODI-20367: Export directory {0} does not exist.

Category:
Other

Cause:
The specified directory does not exist

Action:
Create the directory and repeat the operation

ODI-20368
ODI-20368: WSDL URL is null or empty, ODI can not initialize the current request.

Category:
Other

Cause:
WSDL URL is null

Action:
Set the WSDL URL or remove the soap request.

ODI-20370
ODI-20370 : Shortcuts within a project can only refer to objects that belong to that same project

Category:
Other

Cause:
Shortcuts within a project can only refer to objects that belong to that same project

Action:
=Try another folder destination

ODI-20371
ODI-20371 : No two shortcut objects within a folder may refer to the same base object

Category:
Other

Cause:
No two shortcut objects within a folder may refer to the same base object

Action:
Try another folder destination or fix folder contents

ODI-20372
ODI-20372 : The source and destination models must be defined with the same Technology

Category:
Other

Cause:
The source and destination models must be defined with the same Technology

Action:
Try another model destination or fix model properties.

ODI-20373
ODI-20373 : No two shortcuts within a model may contain the same base object

Category:
Other

Cause:
No two shortcuts within a model may contain the same base object

Action:
Try another folder destination or fix model contents.

ODI-20374
ODI-20374 : A model cannot contain a datastore and a datastore shortcut to another datastore with the same datastore name

Category:
Other

Cause:
A model cannot contain a datastore and a shortcut to another datastore with the same datastore name

Action:
Try another folder destination or fix model contents.

ODI-20701
ODI-20701: The Name field is mandatory.

Category:
Other

Cause:
The Name field was not entered.

Action:
Enter a name for the Load Plan.

ODI-20702
ODI-20702: The name given for the Load Plan is already used by another load plan. Please provide another name.

Category:
Other

Cause:
The name provided for the Load Plan was not unique.

Action:
Enter a unique name for the Load Plan.

ODI-20703
ODI-20703: Variable "{0}" is not found.

Category:
Other

Cause:
The variable could not be found.

Action:
Provide another name for the variable.

ODI-20704
ODI-20704: Datatype of variable "{0}" has been changed.

Category:
Other

Cause:
The datatype of the original variable is different to the datatype of the load plan variable.

Action:
Verify the datatype of the variable and ensure that the types of the original and load plan variables match.

ODI-20705
ODI-20705: This variable is used in one or more case steps. Removing it will trigger deletion of those case steps, and all of their child steps. Do you want to continue?

Category:
Other

Cause:
An attempt was made to remove a variable which is used in one or more case steps.

Action:
To remove the variable and its associated case steps, click Yes. Otherwise, click No, and nothing will be removed.

ODI-20706
ODI-20706: The Step Name is mandatory.

Category:
Other

Cause:
The Step Name field was not entered.

Action:
Enter a name for the Step.

ODI-20707
ODI-20707: The Variable is mandatory.

Category:
Other

Cause:
A Variable was not selected.

Action:
Select a variable.

ODI-20708
ODI-20708: The Scenario is mandatory.

Category:
Other

Cause:
A Scenario was not selected.

Action:
Select a Scenario.

ODI-20709
ODI-20709: The Value is mandatory.

Category:
Other

Cause:
A Value was not provided.

Action:
Enter a Value.

ODI-20710
ODI-20710: The Value format is not valid.

Category:
Other

Cause:
An incorrect format was given for the Value.

Action:
Check the format of the Value and correct it.

ODI-20711
ODI-20711: The Step Name is mandatory.

Category:
Other

Cause:
The Step Name field was not entered.

Action:
Provide the name of the Step.

ODI-20712
ODI-20712: The Variable is mandatory.

Category:
Other

Cause:
A Variable was not selected.

Action:
Select a Variable.

ODI-20713
ODI-20713: The Scenario is mandatory.

Category:
Other

Cause:
A Scenario was not selected.

Action:
Select a Scenario.

ODI-20714
ODI-20714: The Context is mandatory.

Category:
Other

Cause:
A Context was not selected for execution.

Action:
Select an execution Context.

ODI-20715
ODI-20715: The Logical Agent is mandatory.

Category:
Other

Cause:
A Logical Agent was not selected for execution.

Action:
Select a Logical Agent.

ODI-20716
ODI-20716: No Physical Agent is defined for the selected Logical Agent and Context. Edit Logical Agent "{0}", and define a Physical Agent for Context "{1}".

Category:
Other

Cause:
There was no Physical Agent associated with this Logical Agent in the specified context.

Action:
Associate a Physical Agent with the Logical Agent in the selected context.

ODI-20717
ODI-20717: No Physical Agents are running. A Physical Agent must be running in order to Restart a Load Plan.

Category:
Other

Cause:
There were no Physical Agents running.

Action:
Start a Physical Agent before restarting the Load Plan.

ODI-20718
ODI-20718: No Physical Agents are running. A Physical Agent must be running in order to Stop a Load Plan.

Category:
Other

Cause:
There were no Physical Agents running.

Action:
Start the Agent before executing the Load Plan.

ODI-20719
ODI-20719: Scenario "{0}" is not found.

Category:
Other

Cause:
The scenario was not found.

Action:
Specify an existing scenario.

ODI-20720
ODI-20720: Physical Agent "{0}" - which is defined in Logical Agent "{1}" to be used for Context "{2}" - is not responding. Verify that Physical Agent "{0}" has been started.

Category:
Other

Cause:
The Physical Agent was not reachable.

Action:
Check the Physical Agent and start it.

ODI-20721
ODI-20721: Interface contains one or more errors. You should correct the errors before attempting to execute it

Category:
Other

Cause:
The interface contains errors which prevent it from being executed.

Action:
Review the errors shown in the interface editor and update the interface to fix the problems.

ODI-20722
ODI-20722: Cannot display data. Source alias is {0} characters long which is longer than allowed by the technology ({1}). Please review the technology settings in Topology.

Category:
Other

Cause:
Source alias exceeded the limit allowed by its technology.

Action:
Ensure the maximum table name length setting in the corresponding technology is correct. Consider changing source alias to comply.

ODI-20723
ODI-20723: There is no any version of scenario {0} found. A scenario of the step {1} cannot be refreshed.

Category:
Other

Cause:
The scenario of step was not found.

Action:
Check if specified scenario for this step is correct.

ODI-20724
ODI-20724: Journalized data not found. Journal data view: {0}

Category:
Other

Cause:
Journal is not started or is stopped.

Action:
Ensure the journal is started: select Changed Data Capture > Journal Data.

ODI-20726
ODI-20726: The Step Name is mandatory.

Category:
Other

Cause:
The Step Name field was not entered.

Action:
Enter a name for the Step.

ODI-20727
ODI-20727: Scenario "{0}" parent is not found.

Category:
Other

Cause:
The Scenario source object does not exist.

Action:
Check if the source object, from which the Scenario was generated, does exist.

ODI-20728
ODI-20728: The attribute name is mandatory

Category:
Other

Cause:
The datastore attribute could not be saved because the mandatory Name field was not entered.

Action:
Enter a value in the attribute name field.

ODI-20729
ODI-20729: {0} is a dependant object of the following object(s) {1} and cannot be removed

Category:
Other

Cause:
Selected object for removal is a dependent object.

Action:
Remove the dependent object first.

ODI-20731
ODI-20731: The parent from which this scenario is generated does not exist anymore so the editor couldn't show the parent related information.

Category:
Other

Cause:
The editor couldn't show the parent related information because the scenario parent does not exist anymore. This could happen, for example, if you imported the scenario, but didn't import it's parent object.

Action:
Try to figure out, why the scenario parent object does not exist. Try to restore the parent.

ODI-20732
ODI-20732: You cannot move a submodel into another model.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Submodels cannot be moved into hierarchy of another models.

ODI-20733
ODI-20733: You cannot copy a submodel into another model.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Submodels cannot be copied into hierarchy of another models.

ODI-20734
ODI-20734: Changing the name of a user function only impacts the user function itself; Users need to manually change object(s) which reference the old user function name.

Category:
Other

Cause:
The user function name has been updated

Action:
It is the user's responsibility to determine where the user function is referenced and to manually change the name of the user function in those places

ODI-20735
ODI-20735: The name given for the Physical Agent is already used by another agent. Please provide another name

Category:
Other

Cause:
The name provided for the Physical Agent was not unique.

Action:
Enter a unique name for the Physical Agent.

ODI-20736
ODI-20736: The Name field is mandatory.

Category:
Other

Cause:
The value for the Name field was not specified.

Action:
Enter a name for the Object.

ODI-20737
Could not build WSDL Model.

Category:
Other

Cause:
An unexpected error occurred while building a WSDL model.

Action:
Review the error details for further information.

ODI-20741
ODI-20741: This is not a valid Cobol Copybook.

Category:
Other

Cause:
The file chosen in the Reverse Engineering Cobol Copybook process is not a valid Cobol Copybook.

Action:
Ensure the file is a valid Cobol Copybook.

ODI-20742
ODI-20742: You cannot copy a mapping into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Mappings cannot be copied into hierarchy of another projects.

ODI-20743
ODI-20743: You cannot copy a reusable mapping into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Reusable mappings cannot be copied into hierarchy of another projects.

ODI-20744
ODI-20744: You cannot move a mapping into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Mappings cannot be moved into hierarchy of another projects.

ODI-20745
ODI-20745: You cannot move a reusable mapping into a folder belonging to another project.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Reusable mappings cannot be moved into hierarchy of another projects.

ODI-20746
ODI-20746: You cannot move a global reusable mapping into a folder.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Global Reusable mappings cannot be moved into a folder.

ODI-20747
ODI-20747: You cannot copy a global reusable mapping into a folder.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Global Reusable mappings cannot be copied into a folder.

ODI-20748
ODI-20748: Open is not valid for this node.

Category:
Other

Cause:
The editor is not applicable for this node.

Action:
Editor cannot be opened for this node.

ODI-20749
ODI-20749: Selected Capture/Initial Load Capture process is associated with another model. This may cause conflicts during 'Start Journal' action, if the logical process instance selected uses the same physical process instance.

Category:
Other

Cause:
Selected Goldengate Capture/Initial Load Capture process is used in a different model.

Action:
Select a different set of process instances for this model.

ODI-20750
ODI-20750: Selected Delivery/Initial Load Delivery process is associated with another model. This may cause conflicts during 'Start Journal' action, if the logical process instance selected uses the same physical process instance.

Category:
Other

Cause:
Selected Goldengate Delivery/Initial Load Delivery process is used in a different model.

Action:
Select a different set of process instances for this model.

ODI-20751
ODI-20751: Load Plan Debugging is not supported: {0}.

Category:
Other

Cause:
An unsupported operation was attempted.

Action:
Load Plan can't be debug.

ODI-20752
ODI-20752: Format can not be empty for File datastore's Date type column

Category:
Other

Cause:
Column added for the File datastore has Date as type but Format is not given

Action:
Ensure the Format is entered for File datatsore's column of type Date.

ODI-20753
ODI-20753 : Shortcuts in a Model can not be moved

Category:
Other

Cause:
Shortcuts in a Model can not be moved to another Model

Action:
Please get the base object of the shortcut first and then try to move

ODI-20754
ODI-20754 : Driver name cannot be empty

Category:
Other

Cause:
Driver is not assigned for the Data Server

Action:
Please choose the appropriate driver for the datastore.

ODI-20755
ODI-20755: A Data Server with the name {0} already exists. Please provide another name.

Category:
Other

Cause:
The name provided for the Data Server is not unique.

Action:
Enter a unique name for the Data Server.

ODI-20756
ODI-20756: A Logical Schema with the name {0} already exists. Please provide another name.

Category:
Other

Cause:
The name provided for the Logical Schema is not unique.

Action:
Enter a unique name for the Data Server.

ODI-20757
ODI-20757: If logical schema is specified, WSDL URL can not differ from physical schema's WSDL URL.

Category:
Other

Cause:
You have specified different WSDL URL compared to physical schema WSDL URL.

Action:
WSDL URL and physical schema WSDL URL should be same when logical schema is specified.

ODI-20758
ODI-20758: If logical schema is specified, HTTP User can not differ from physical schema's/ data server's HTTP User.

Category:
Other

Cause:
You have specified different user compared to physical schema/data server HTTP user.

Action:
User and physical schema/data server HTTP user should be same when logical schema is specified.

ODI-20759
ODI-20759: If logical schema is specified, Port Type can not differ from physical schema's port type.

Category:
Other

Cause:
You have specified different port type compared to physical schema port type.

Action:
Port type and physical schema port type should be same when logical schema is specified.

ODI-20760
ODI-20760: Choice names should be unique.

Category:
Other

Cause:
You have added duplicate choice names.

Action:
Ensure only unique choice names are used.

ODI-20761
ODI-20761: An Option Group with the name {0} already exists. Please provide another name.

Category:
Other

Cause:
The name provided for the Option Group is not unique.

Action:
Enter a unique name for the Option Group.

ODI-20763
ODI-20763: Maximum number of login attempts reached. ODI User will be locked.

Category:
Other

Cause:
You have exceeded the maximum number of login attempts.

Action:
A Supervisor user must unlock this user.

ODI-20764
ODI-20764: Error occurred while creating version for regenerated Scenario.

Category:
Other

Cause:
Auto versioning failed for the regenerated Scenario

Action:
Please check log for more information

ODI-20765
ODI-20765: Agent Invocation Failed.

Category:
Other

Cause:
ODI Agent request invocation failed.

Action:
Ensure Agent is in correct state.

ODI-20766
ODI-20766: ODI does not support View Data for Non-JDBC datastore

Category:
Other

Cause:
ODI does not support View Data for Non-JDBC datastore

Action:
View Data for Non-JDBC datastore is not supported

ODI-23001
ODI-23001: The import process failed

Category:
Other

Cause:
The work repository export file specified could not be imported.

Action:
Ensure the specified file is readable and is a valid work repository export file.

ODI-23006
ODI-23006: Agent Test failed

Category:
Other

Cause:
Agent could not be contacted using the specified connection details.

Action:
Ensure the Agent connection details are correct and the Agent is running.

ODI-23007
ODI-23007: Data Source already exists for "{0}".

Category:
Other

Cause:
The Data Source has already been associated with this Agent.

Action:
No action is necessary as the Data Source is already associated with this Agent. Consider removing the Data Source from this Agent and retrying this action.

ODI-23010
ODI-23010: Please enter first a name, an expression and a help text for this language element.

Category:
Other

Cause:
The Name, Expression or Help Text parameter values for this Language Element were not entered in the Definition panel. These are mandatory parameters.

Action:
Return to the Definition panel and ensure the Name, Expression and Help Text parameters have valid values.

ODI-23011
ODI-23011: Name is empty

Category:
Other

Cause:
A value for the Name parameter of the Language Element Implementation was not entered. This is a mandatory parameter.

Action:
Enter a valid value for the Name parameter before saving this Language Element.

ODI-23012
ODI-23012: Expression is empty

Category:
Other

Cause:
A value for the Expression parameter of the Language Element Implementation was not entered. This is a mandatory parameter.

Action:
Enter a valid value for the Expression parameter before saving this Language Element.

ODI-23013
ODI-23013: Help is undefined

Category:
Other

Cause:
A value for the Help Text parameter of the Language Element Implementation was not entered. This is a mandatory parameter.

Action:
Enter a value for the Help Text parameter before saving this Language Element.

ODI-23014
ODI-23014: Technology is undefined

Category:
Other

Cause:
A value for the Technology parameter of the Language Element Implementation was not entered. This is a mandatory parameter.

Action:
Enter a value for the Technology parameter before saving this Language Element.

ODI-23015
ODI-23015: Logical Schema {0} is already linked to a physical schema in context {1}.

Category:
Other

Cause:
A Physical Schema has already been defined for this Context and Logical Schema combination.

Action:
Remove the Context and Logical Schema combination from the Context editor, then retry saving the Physical Schema.

ODI-23016
ODI-23016: The context is either invalid or no longer exists in the database.

Category:
Other

Cause:
One of the Contexts used by the Physical Schema is invalid or no longer exists in the Master Repository.

Action:
Ensure the Context for the Physical Schema is correct by either selecting a valid Context for the Physical Schema or recreating the missing Context.

ODI-23017
ODI-23017: This Physical Schema already exists for this data server.

Category:
Other

Cause:
A Physical Schema referencing this Data Server has already been defined in the Master Repository.

Action:
Specify the correct Physical Schema for this Data Server to use.

ODI-23018
ODI-23018: Unable to connect to Work Repository.Repository host or database is not available.

Category:
Other

Cause:
The Work Repository could not be accessed using the connection details defined for it. This may be due to the database or host not being available, or the password could have changed.

Action:
Ensure the Work Repository host and database are active. Using the Work Repository editor, ensure the connection details for it are correct.

ODI-23019
ODI-23019: Error Detected during Repository Installation. Invalid connection parameters.

Category:
Other

Cause:
The repository installation process was unable to connect to the repository database.

Action:
Correct any errors identified in the installation log and retry the installation. If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

ODI-23020
ODI-23020: Error Detected during Repository Installation. Invalid External Authentication credentials.

Category:
Other

Cause:
The ODI Supervisor credentials supplied did not match the credentials held in the External Password Store.

Action:
Retry the installation, ensuring the Supervisor user name and password match those held in the external store.

ODI-23021
ODI-23021: Error Detected during Repository Installation. Invalid External Authentication configuration.

Category:
Other

Cause:
A connection to the External Authentication Store could not be established.

Action:
Ensure the External Authentication Store is available and the connection details specified in the JPS configuration file are valid.

ODI-23022
ODI-23022: An error occurred during the generation of the Data Service.

Category:
Other

Cause:
An unexpected error occurred while generating data services.

Action:
Review the error details for further information.

ODI-23023
ODI-23023: The Schema path ({0}) is not supported

Category:
Other

Cause:
The Model's Physical Schema attempted to define the Schema path using an unsupported protocol (ftp, http or file).

Action:
Change the Physical Schema to not use ftp, http or file protocol to reference the file.

ODI-23024
ODI-23024: The URL is mandatory.

Category:
Other

Cause:
The URL field has not been entered and is a mandatory parameter.

Action:
Enter the URL parameter. A template chosen from the drop down list may help to ensure the syntax is correct.

ODI-23025
ODI-23025: The ID is mandatory.

Category:
Other

Cause:
The Repository ID parameter has not been entered and is a mandatory parameter.

Action:
Enter an integer value for the Repository ID parameter.

ODI-23026
ODI-23026: The ID must be an integer value.

Category:
Other

Cause:
The value entered for the Repository ID is not a valid integer.

Action:
Enter an integer value for the Repository ID parameter.

ODI-23027
ODI-23027: The driver is mandatory.

Category:
Other

Cause:
A JDBC Driver was not specified and is a mandatory parameter.

Action:
Select a JDBC Driver from the list of values.

ODI-23028
ODI-23028: The password is mandatory.

Category:
Other

Cause:
The Supervisor user's Password parameter was not specified.

Action:
Enter the Supervisor password.

ODI-23029
ODI-23029: The confirm password is mandatory.

Category:
Other

Cause:
The Supervisor user's Confirm Password parameter was not specified.

Action:
Enter the Supervisor user's password in the Confirm Password parameter.

ODI-23030
ODI-23030: Password and Confirm Password are different

Category:
Other

Cause:
The Password and Confirm Password parameters are not the same.

Action:
Ensure the same value is entered for both the Password and Confirm Password parameters.

ODI-23031
ODI-23031: The Supervisor username is mandatory.

Category:
Other

Cause:
The Supervisor User parameter was not entered.

Action:
Enter a value for the Supervisor User parameter ensuring it matches a user in the external enterprise identify store, or switch to ODI Authentication.

ODI-23032
ODI-23032: Maximum number of sessions cannot be less or equal to 0.

Category:
Other

Cause:
The Maximum Number of Sessions parameter value was specified as 0.

Action:
Change the Maximum Number of Sessions parameter in the Agent Definition tab to a value greater than 0.

ODI-23033
ODI-23033: The file reverse-engineering is only possible for delimited files.

Category:
Other

Cause:
The file format for the specified file was not delimited.

Action:
Select a delimited format file and retry the reverse-engineering action.

ODI-23035
ODI-23035: Can not update the scheduling - This agent may not be running

Category:
Other

Cause:
The Update Scheduling action could not be performed because the ODI Client could not connect to the Agent.

Action:
Check that the Agent connection details are correct and that the agent is running. Use the Agent Test button to check the connection details.

ODI-23036
ODI-23036: Logical Schema not set for Context

Category:
Other

Cause:
A Logical Schema entry in the Physical Schema's Context was specified as <Undefined>.

Action:
Ensure none of the Logical Schemas on the Physical Schema's Context tab are set to <Undefined>.

ODI-23037
ODI-23037: To use scheduling please associate a Logical Agent to a Physical Agent via the Logical Architecture Accordion in the Topology Navigator

Category:
Other

Cause:
There are no logical agents available to use for scheduling.

Action:
Associate a logical agent with a physical agent using the Topology Navigator and then resubmit your schedule request.

ODI-23038
ODI-23038: Cannot resolve the table name. Check the masks defined for this physical schema.

Category:
Other

Cause:
The table and schema format could not be calculated. This is because the object mask has not been set for the Physical Schema that contains this table.

Action:
From the Topology Navigator edit the Physical Schema containing this table and ensure the Masks parameter value is valid for the schema based on its technology (for example "%SCHEMA.%OBJECT").

ODI-23039
ODI-23039: You cannot carry out this type of export.

Category:
Other

Cause:
The export type specified is not supported.

Action:
Retry the export. If the problem persists then contact Oracle Support Services.

ODI-23040
ODI-23040: Import file "{0}" error

Category:
Other

Cause:
An error occured during the import file process.

Action:
Correct any errors identified in the error log and retry the import process. If the problem persists then contact Oracle Support Services.

ODI-23042
ODI-23042: An error occurred while changing the repository number.

Category:
Other

Cause:
An error occured while changing the repository number.

Action:
Correct any errors identified in the message log and retry the action. If the problem persists then contact Oracle Support Services.

ODI-23043
ODI-23043: The Repository ID must be numeric.

Category:
Other

Cause:
The value specified for the Repository ID parameter was not a valid numeric value.

Action:
Enter a valid numeric value for the Repository ID parameter.

ODI-23044
ODI-23044: The new ID you have chosen is already in use as a table "{0}" primary key. The renumbering has been aborted. No changes have been made.

Category:
Other

Cause:
The Repository ID specified is already used by an existing object.

Action:
Enter a different value for the Repository ID parameter ensuring it is unique within the repository.

ODI-23045
ODI-23045: You may not renumber a repository before version 11. Please upgrade your repository first.

Category:
Other

Cause:
The renumber functionality is not supported for ODI Repository versions prior to version 11.

Action:
Upgrade the repository to version 11 (or higher) and then renumber it.

ODI-23046
ODI-23046: An error was encountered during the test.

Category:
Other

Cause:
An attempt to connect a Work Repository failed.

Action:
Correct any errors identified in the message log. Ensure the Work Repositories are available and the connection information is correctly specified in the Master Repository. Retry the test.

ODI-23047
ODI-23047: Could not connect to the work repository. The renumbering process has been aborted. No changes have been made.

Category:
Other

Cause:
An attempt to connect a Work Repository failed.

Action:
Correct any errors identified in the message log. Ensure the Work Repositories are available and the connection information is correctly specified in the Master Repository. Retry the test.

ODI-23048
ODI-23048: Import report generation error

Category:
Other

Cause:
The import was performed, but there was an unexpected error while opening the Import Report.

Action:
Contact Oracle Support Services.

ODI-23049
ODI-23049: Error Detected during Repository Installation

Category:
Other

Cause:
An error occured during the creation or import of the Master Repository.

Action:
Correct any errors described in the message log and retry the installation process. If this is caused by an external application, then fix the related code; otherwise, contact My Oracle Support.

ODI-23050
ODI-23050: The password you entered doesn't match the actual password

Category:
Other

Cause:
The password you entered doesn't match the actual password

Action:
Ensure that the password entered matches the actual password

ODI-23051
ODI-23051: Maximum number of threads must be greater than zero.

Category:
Other

Cause:
Values for maximum number of threads is not valid

Action:
Enter valid value for maximum number of threads

ODI-23052
ODI-23052: Maximum number of thread per session cannot be less than 0.

Category:
Other

Cause:
Values for maximum number of thread per session is not valid

Action:
Enter valid value for maximum number of threads per session

ODI-23053
ODI-23053: Maximum number of threads cannot be less than maximum number of threads per session.

Category:
Other

Cause:
Maximum number of threads less than maximum number of threads per session

Action:
Enter valid values for maximum number of threads and maximum number of threads per session

ODI-23054
ODI-23054: Maximum number of cache entries cannot be less than zero.

Category:
Other

Cause:
Values for maximum number of cache entries is not valid

Action:
Enter valid values for maximum number of cache entries

ODI-23055
ODI-23055: Session Blueprint Lifetime cannot be less than zero.

Category:
Other

Cause:
Value for session blueprint lifetime is not valid

Action:
Enter valid values forsession blueprint lifetime

ODI-23056
ODI-23056: Syntax of condition "{0}" is not valid.

Category:
Other

Cause:
The entered condition has invalid syntax.

Action:
Specify the valid condition expression.

ODI-23057
ODI-23057: The Registry Database is mandatory for MySQL Technology.

Category:
Other

Cause:
The Registry Database was not specified for MySQL Technology.

Action:
Enter the Registry Database for MySQL Technology.

ODI-23058
ODI-23058: This Technology does not support multiple schemas.

Category:
Other

Cause:
Attempt to create multiple Physical Schemas for Technologies that support only one Schema.

Action:
The solution for Technologies that do not support multiple Physical Schemas is to create separate Data Dervers from the Physical Schemas.

ODI-23059
ODI-23059: No Agent selected

Category:
Other

Cause:
No Agent has been selected for the selected DataSource.

Action:
Make sure an Agent is selected for the DataSource.

ODI-23060
ODI-23060: Update Import Modes are not valid for Interfaces

Category:
Other

Cause:
An invalid import mode of Update is selected for an Interface export file.

Action:
Use an import mode other than Update or alternatively only import Mapping export files

ODI-23061
ODI-23061: Syntax of expression "{0}" is not valid.

Category:
Other

Cause:
The entered expression has invalid syntax.

Action:
Specify the valid expression.

ODI-23062
ODI-23062: Maximum number of threads cannot be less then the maximum number of sessions.

Category:
Other

Cause:
Value for maximum number of threads is less than the maximum number of sessions

Action:
Ensure that maximum number of threads is equal to or greater than the maximum number of sessions

ODI-23064
ODI-23064 Language Name must be specified

Category:
Other

Cause:
Language name is not specified.

Action:
Enter Language name on the Languages table.

ODI-23065
ODI-23065 Parameter Key names not unique

Category:
Other

Cause:
Invalid values.

Action:
Parameter values need to be valid including uniquenames for keys.

ODI-23066
ODI-23066: Letter used in the icon input "{0}" is not valid. No Special Characters are allowed to be entered.

Category:
Other

Cause:
The entered input is invalid.

Action:
Enter the valid value.

ODI-23068
ODI-23068 : Degree Of Parallelism For Target has to be in the range of 1 to 99.

Category:
Other

Cause:
Value entered for Degree Of Parallelism is not in the range 1-99.

Action:
Please choose the appropriate Degree Of Parallelism For Target.

ODI-23069
ODI-23069 : Web Application Context must be provided

Category:
Other

Cause:
No value entered for the Web Application Context.

Action:
Please enter value for the Web Application Context.

ODI-23070
ODI-23070: Port number must be an integer between 0 and 65535.

Category:
Other

Cause:
The value for the Port Number was not valid.

Action:
Enter a valid integer value between 0 and 65535 for the Port Number.

ODI-23071
ODI-23071: Invalid Override Endpoint URL.

Category:
Other

Cause:
Override Endpoint URL enterred is invalid.

Action:
Please enter a valid Override Endpoint URL.

ODI-23072
ODI-23072: Invalid WSDL URL.

Category:
Other

Cause:
WSDL URL enterred is invalid.

Action:
Please enter a valid WSDL URL.

ODI-23073
ODI-23073: Duplicate Operation Names exist.

Category:
Other

Cause:
Duplicate Operation Names exist

Action:
Please ensure that operation names are unique.

ODI-23074
ODI-23074: The JNDI driver is mandatory.

Category:
Other

Cause:
A JNDI Driver was not specified and is a mandatory parameter.

Action:
A JNDI Protocol chosen from the drop down list may help to ensure the syntax is correct.

ODI-23075
ODI-23075: The JNDI URL is mandatory.

Category:
Other

Cause:
The JNDI URL field has not been entered and is a mandatory parameter.

Action:
Enter the URL parameter. A template chosen from the drop down list may help to ensure the syntax is correct.

ODI-23076
ODI-23076: The JNDI Resource is mandatory.

Category:
Other

Cause:
The JNDI Resource field has not been entered and is a mandatory parameter.

Action:
Enter the Resource parameter.

ODI-23077
ODI-23077: Please enter Credential file password.

Category:
Other

Cause:
Credential file password is a mandatory parameter for ewallet.p12.

Action:
Enter the credential file password.

ODI-23078
ODI-23078: Could not fetch details from Credential file. Please check logs for further details.

Category:
Other

Cause:
Error occurred while fetching details from Credential file.

Action:
Please check logs.

ODI-23079
ODI-23079: Invalid Credential file.

Category:
Other

Cause:
Valid credential file not found.

Action:
Please provide valid credential file path.

ODI-23080
ODI-23080: Credential file is not accessible.

Category:
Other

Cause:
Credential file does not have required permissions.

Action:
Please provide required permissions to Credential file.

ODI-23081
ODI-23081: Credential file could not be found at given path.

Category:
Other

Cause:
Credential file is not found in given path.

Action:
Please provide correct Credential file path.

ODI-23082
ODI-23082: Unable to retrieve credentials, the connection information does not match with any of the entries in Credential file.

Category:
Other

Cause:
Connection information does not match with any of the entries in Credential file.

Action:
Verify Credential file.

ODI-23083
ODI-23083: No connection information found in Credential file.

Category:
Other

Cause:
Credential file is empty.

Action:
Verify Credential file.

ODI-23084
ODI-23084: Please select an Oracle database connection.

Category:
Other

Cause:
No selection made.

Action:
Select Oracle database connection.

ODI-23085
ODI-23085: Entered password does not match Credential file password.

Category:
Other

Cause:
Credential file password is not valid.

Action:
Please try again.

ODI-24004
ODI-24004: There are no supervisor accounts in the ODI repository with matching entries in the identity store. Please provide a suitable supervisor account. Or you may also want to double check your JPS configuration file e.g. jps-config-jse.xml regarding the identity store configuration on properties such as {0}.

Category:
Other

Cause:
The ODI repository does not have any supervisor account that matches the entries in the identity store based on the identity store configuration from JPS configuration file.

Action:
Create a supervisor account in the ODI repository that matches an entry in the identify store. Or you may also want to double check your JPS configuration file e.g. jps-config-jse.xml file regarding the identity store configuration on properties such as username.attr, groupname.attr, user.search.bases, group.search.bases.

ODI-24005
ODI-24005: An error occurred while checking the status of the master repository.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Check the exception to see if it gives details about the error and contact Oracle Support Services for further assistance.

ODI-24006
ODI-24006: An error occurred while switching the authentication mode for the master repository.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Check the exception to see if it gives details about the error and contact Oracle Support Services for further assistance.

ODI-24007
ODI-24007: Rules should not have empty conditions.

Category:
Other

Cause:
Rules associated with policy have empty conditions.

Action:
Create rules with conditions associated with them.

ODI-25001
ODI-25001: Unable to input a larger element

Category:
Other

Cause:
The total length of all keywords exceeds the maximum length.

Action:
Remove one or more of the keywords, or decrease their lengths.

ODI-25002
ODI-25002: The end date cannot be before the start date.

Category:
Other

Cause:
The end date is before the start date.

Action:
Set the end date to be after the start date.

ODI-25003
ODI-25003: Error while starting session

Category:
Other

Cause:
An unexpected error occured while starting the session.

Action:
Check the error details for further information and contact Oracle Support Services for further assistance.

ODI-25004
ODI-25004: Date Format Not Valid

Category:
Other

Cause:
One of the Date fields is invalid. This may be the From or To Date.

Action:
Click the button to the right of the field to invoke a dialog for entering a valid Time and Date.

ODI-25005
ODI-25005: Incorrect date format . The format is {0}.

Category:
Other

Cause:
The date format is incorrect.

Action:
Use the format that is presented in the error message.

ODI-25006
ODI-25006: At least one agent must be selected.

Category:
Other

Cause:
Agent selection is mandatory.

Action:
Select at least one agent to clean stale sessions.

ODI-25007
ODI-25007: At least one work repository must be selected.

Category:
Other

Cause:
Work repository selection is mandatory.

Action:
Select at least one work repository to clean stale sessions.

ODI-25008
ODI-25008: You are not allowed to delete session variable.

Category:
Other

Cause:
User attempt to delete session variable.

Action:
Cancel deleting session variable.

ODI-25009
ODI-25009: You are not allowed to delete scenario variable.

Category:
Other

Cause:
User attempt to delete scenario variable.

Action:
Cancel deleting scenario variable.

ODI-26001
ODI-26001: Boolean does not correspond to the Field Update Object Layer.

Category:
Other

Cause:
The repository contained an invalid value of the Field Update property for a checkbox or radio group.

Action:
Ensure the repository value is a boolean for checkbox or a valid action command for a radio group.

ODI-26002
ODI-26002: This object is referenced by another object. View the details for more information. You may also see where this object is used in the hierarchy.

Category:
Other

Cause:
The specified object could not be used because it is referenced by another object.

Action:
Remove references to this object. The "Uses" hierarchy may be useful in finding objects references.

ODI-26003
ODI-26003: This object cannot be removed: it is referenced by another object.

Category:
Other

Cause:
The specified object could not be deleted because it is referenced by another object.

Action:
Remove references to this object before deleting it. The "Uses" hierarchy may be useful in finding objects references.

ODI-26004
ODI-26004: Action denied:

Category:
Other

Cause:
The current license may not allow use of the designer.

Action:
Review the error details for further information.

ODI-26005
ODI-26005: You are importing an object from another repository with the same identifier. It is forbidden.

Category:
Other

Cause:
An object in the import file has an identifier which already exists in the repository.

Action:
Consider manually changing the "com.sunopsis.dwg.dwgobj.SnpImportRep" object section of the import XML file to use a unique identifier.

ODI-26006
ODI-26006: The specified encryption key is invalid.

Category:
Other

Cause:
The encryption key specified was found to be invalid during the decrypting phase.

Action:
Ensure a valid encryption key is utilized.

ODI-26007
ODI-26007: KM or Procedure not encrypted. No decryption was performed.

Category:
Other

Cause:
Decryption was requested for a non-encypted KM or Procedure.

Action:
Do not attempt to decrypt a non-encrypted KM or Procedure.

ODI-26008
ODI-26008: Scenario not encrypted. No decryption was performed.

Category:
Other

Cause:
Decryption was requested for a non-encypted Scenario.

Action:
Do not attempt to decrypt a non-encrypted Scenario.

ODI-26009
ODI-26009: Action not encrypted. No decryption was performed.

Category:
Other

Cause:
Decryption was requested for a non-encypted Action.

Action:
Do not attempt to decrypt a non-encrypted Action.

ODI-26010
ODI-26010: Decryption failed due to incompatible key.

Category:
Other

Cause:
The key provided to decrypt was an invalid key.

Action:
Ensure the decryption key is correctly specified.

ODI-26011
ODI-26011: unable to find specified encryption API

Category:
Other

Cause:
The specified cryptographic algorithm requested was not available in the environment.

Action:
Ensure the environment can access the DES/ECB/PKCS5Padding algorithms and padding.

ODI-26012
ODI-26012: invalid encrypted data.

Category:
Other

Cause:
The BASE64 content may be invalid or the zip file contents may be corrupted.

Action:
Ensure the encrypted data is correct and the decryption key is correctly specified.

ODI-26013
ODI-26013: Your security parameters are insufficient to perform this action.

Category:
Other

Cause:
The ODI user security parameters do not specifically permit the user to perform this particular action.

Action:
Ensure this ODI user is granted the security access to perform this action.

ODI-26014
ODI-26014: The code of your {0} is already used by another {1}. Please give another code to save this {2}.

Category:
Other

Cause:
The value entered for code must be unique for the entire work repository.

Action:
Ensure the a unique value is entered.

ODI-26015
ODI-26015: You do not have sufficient privileges to perform this operation.

Category:
Security

Cause:
The ODI user security parameters do not specifically permit the user to perform this particular operation.

Action:
Ensure this ODI user is granted the security access to perform this operation.

ODI-26016
ODI-26016: The requested operation cannot succeed. The object no longer exists.

Category:
Other

Cause:
The specified ODI object cannot be accessed because it no longer exists in the repository (it may have been deleted by another ODI user).

Action:
Recreate the specified ODI object. Consider importing the object from a backup.

ODI-26017
ODI-26017: Error.

Category:
Other

Cause:
Internal error.

Action:
Review the error details for further information.

ODI-26018
ODI-26018: Key Error.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Review the error details for further information.

ODI-26019
ODI-26019: Action Denied.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Review the error details for further information.

ODI-26020
ODI-26020: Retrieve method incorrect.

Category:
Other

Cause:
Retrieve method is incorrect. Must be "set" or "get".

Action:
Please change the retrieve method to "set" or "get".

ODI-26021
ODI-26021: Object initialization denied.

Category:
Other

Cause:
A component could not be initialized.

Action:
Ensure that the user has security permissions to create the object.

ODI-26022
ODI-26022: Unrecoverable error during object saving.

Category:
Other

Cause:
The object could not be saved. This is possibly due to a repository connection error, or inconsistent data values supplied. It's also possible that the object was modified by another user.

Action:
Ensure the repository database is available and the data values supplied are valid. Try to save changed data, then refresh edited object and apply changed data again.

ODI-26023
ODI-26023: Cannot create object.

Category:
Other

Cause:
An unexpected error occured during the object creation process.

Action:
Contact Oracle Support Services.

ODI-26024
ODI-26024: Cannot stop update operation.

Category:
Other

Cause:
An unexpected error occured during the update operation.

Action:
Contact Oracle Support Services.

ODI-26025
ODI-26025: Display Initialization denied.

Category:
Other

Cause:
An unexpected error occured during the display initialization process.

Action:
Contact Oracle Support Services.

ODI-26026
ODI-26026: Cannot refresh.

Category:
Other

Cause:
An unexpected error occured during the refresh process.

Action:
Contact Oracle Support Services.

ODI-26027
ODI-26027: Security not set for the instance. The instance will not be added to the tree.

Category:
Security

Cause:
Instance security permissions "By repository" were choosen but a concrete repository is not specified.

Action:
Ensure a repository is specified.

ODI-26028
ODI-26028: Cannot save your modifications.

Category:
Other

Cause:
Internal error.

Action:
No action required.

ODI-26029
ODI-26029: Could not deploy the datasource automatically.

Category:
Other

Cause:
Weblogic Administration server is not up and running, the server connection parameters are wrong.

Action:
Please check Weblogic Administration server connection parameters and the server state.

ODI-26030
ODI-26030: The new password does not meet the password policy. Your change could not be saved.

Category:
Other

Cause:
The new password does not meet the password policy.

Action:
Please verify that the new password meets the password policy (go to the "Security Navigator -> Password policies...").

ODI-26031
ODI-26031: You may not delete work repository {0} because you are connected to it. To delete this repository, reconnect to a different work repository or use a master repository only connection.

Category:
Other

Cause:
Deletion of a work repository which is currently connected is not supported.

Action:
Disconnect from the repository and then connect utilizing a Master Repository Only connection or a different work repository before attempting to delete the specified work repository.

ODI-26032
ODI-26032: This object was modified by {0} on {1} at {2}. Your changes cannot be saved.

Category:
Other

Cause:
The object was changed in the repository after the editor was opened for this object.

Action:
Close the editor without saving changes. Open the editor again and reapply the edits and save. Note: consider using the lock object facility to disallow current modifications to an object.

ODI-26033
ODI-26033: You cannot edit this object because it is locked by another user ({0}). You can only view it.

Category:
Other

Cause:
The ODI object opened for editing is locked by another user. Other ODI users can only view such objects.

Action:
Try to edit the object later.

ODI-26034
ODI-26034: An error occurred while deleting executions.

Category:
Other

Cause:
The specified executions could not be deleted. This is possibly caused by the repository database connection problems.

Action:
Retry to delete the executions. If problem persists, contact Oracle Support Services.

ODI-26035
ODI-26035: Error.

Category:
Other

Cause:
Internal error.

Action:
Review the error details for further information.

ODI-26036
ODI-26036: Error while encrypting.

Category:
Other

Cause:
A general error occured during the ecrypting process, possibly caused by caused by repository database access problems, lack of security permissions, or encryption engine failures,

Action:
Retry the encrypt action again.

ODI-26037
ODI-26037: Encryption key is not valid.

Category:
Other

Cause:
An invalid encryption key was entered causing an encryption engine failure.

Action:
Enter a valid encryption key and retry the action.

ODI-26038
ODI-26038: Unable to execute, the selected Logical Agent is not associated to a Physical Agent in the desired Context.

Category:
Other

Cause:
A Logical Agent was not associated with this Physical Agent in this Context.

Action:
Ensure a valid "Logical Agent - Physical Agent" association exists in the desired Context.

ODI-26039
ODI-26039: Connection failed.

Category:
Other

Cause:
The attempt to connect to the repository failed. This may be due to one or more of the following: invalid connection parameters specified, database problems, network problems.

Action:
Ensure the repository database is available and acceccesible and the repository connection parameters are correct.

ODI-26040
ODI-26040: error while updating

Category:
Other

Cause:
Failed to update the ODI logins file: snps_login_work.xml.

Action:
Ensure write-access is granted to the ODI logins file: snps_login_work.xml.

ODI-26041
ODI-26041: Error while attempting to get FieldData from ObjectDisplay.

Category:
Other

Cause:
An unexpected error occured obtaining FieldData from ObjectDisplay.

Action:
Contact Oracle Support Services.

ODI-26042
ODI-26042: Error while attempting to set FieldUpdate from ObjectUpdate.

Category:
Other

Cause:
An unexpected error occured updating FieldUpdate from ObjectUpdate.

Action:
Contact Oracle Support Services.

ODI-26043
ODI-26043: Window closing cancelled by the User.

Category:
Other

Cause:
User asked to close the parent window where child lines were modified.

Action:
No action performed on that.

ODI-26044
ODI-26044: Host Variable Not Found.

Category:
Other

Cause:
An unexpected error occurred searching for a host variable.

Action:
Review the error details for further information.

ODI-26045
ODI-26045: Unable to perform the drop operation.

Category:
Other

Cause:
Dropped entity is invalid.

Action:
Check whether the dropped entity is valid and perform the drag-n-drop action again.

ODI-26046
ODI-26046: MethodGetter was not found

Category:
Other

Cause:
An unexpected error occured obtaining the getter method.

Action:
Contact Oracle Support Services.

ODI-26047
ODI-26047: Object on method setObjectDisplay(Object pObjectDisplay) is not an array.

Category:
Other

Cause:
This is caused by programmatic error.

Action:
ODI users should normally never see this message.

ODI-26048
ODI-26048: Object on method setObjectDisplay(Object pObjectDisplay) is not a vector.

Category:
Other

Cause:
This is caused by programmatic error.

Action:
ODI users should normally never see this message.

ODI-26049
ODI-26049: Parameters not valid.

Category:
Other

Cause:
An unexpected error occured due to an invalid parameter value.

Action:
Contact Oracle Support Services.

ODI-26050
ODI-26050: Master repository not installed on this connection.

Category:
Other

Cause:
This is caused by programmatic error.

Action:
ODI users should normally never see this message.

ODI-26051
ODI-26051: XML Export Error.

Category:
Other

Cause:
An error occured during the creation of the XML Export file.

Action:
Ensure the repository is accessible and the export file and its directory are writable.

ODI-26052
ODI-26052: XML Import Error.

Category:
Other

Cause:
An unexpected error occurred while importing an XML document.

Action:
Review the error details for further information.

ODI-26053
ODI-26053: An error occurred during initialization.

Category:
Other

Cause:
Initialization failed possibly due a repository access failure or insufficient ODI security permissions.

Action:
Ensure the repository database is available, and the ODI user security permissions permit connection.

ODI-26054
ODI-26054: Page not available.

Category:
Other

Cause:
The selected page number was invalid.

Action:
Ensure the page number entered is greater than 0 and less than the total number of pages.

ODI-26056
ODI-26056: Error while disconnecting.

Category:
Other

Cause:
This error is occured while closing the repository database connection after "Test query" action completed.

Action:
This error may be ignored.

ODI-26057
ODI-26057: Unable to connect the agent. The agent is probably not started.

Category:
Other

Cause:
The connection request to the agent failed.

Action:
Ensure the agent is started and available. Ensure the connection information is valid.

ODI-26058
ODI-26058: Unable to connect the agent. The agent URL cannot be found.

Category:
Other

Cause:
The connection request to the agent failed using the given URL.

Action:
Ensure the agent is started and available. Ensure the connection URL information is valid.

ODI-26059
ODI-26059: Object on method setObjectDisplay(Object pObjectDisplay) is not a List.

Category:
Other

Cause:
An unexpected error occured setting ObjectData.

Action:
Contact Oracle Support Services.

ODI-26060
ODI-26060: The Password and Confirmation Password do not match.

Category:
Other

Cause:
The values entered for Password and Confirmation Password did not match.

Action:
Enter the same value for Password and Confirmation Password.

ODI-26061
ODI-26061: The minimum password length is {0} characters.

Category:
Other

Cause:
The length of the Password entered is less than specified in password policy rule.

Action:
Enter a Password whose length is greater than or equal to the specified minimum length.

ODI-26062
ODI-26062: The password violates the following rule: "{0}". Select another password.

Category:
Other

Cause:
The password supplied was invalid.

Action:
Enter a valid password.

ODI-26063
ODI-26063: Invalid password.

Category:
Other

Cause:
The password supplied was invalid.

Action:
Enter a valid password.

ODI-26064
ODI-26064: Error while exporting.

Category:
Other

Cause:
An error occured during the creation of the Export file.

Action:
Ensure the repository is accessible and the export file and its directory are writable.

ODI-26065
ODI-26065: You must specify all the options.

Category:
Other

Cause:
This is caused by programmatic error.

Action:
ODI users should normally never see this message.

ODI-26066
ODI-26066: An unexpected error has occurred.

Category:
Other

Cause:
An unexpected error occured this process.

Action:
Retry action. If problem persists then contact Oracle Support Services.

ODI-26067
ODI-26067: mandatory field "Java charset" not entered

Category:
Other

Cause:
A value for the "Java character set" field was not entered.

Action:
Enter a value for the "Java character set" field.

ODI-26068
ODI-26068: unable to load export list in the module: {0}

Category:
Other

Cause:
The contents of the export file list was not formatted correctly.

Action:
Correct the format of the export list file specified.

ODI-26069
ODI-26069: The specified export directory does not exist.

Category:
Other

Cause:
The specified export directory is invalid.

Action:
Ensure the specified export directory exists and is writable.

ODI-26070
ODI-26070: The Open Tool class name must not begin with "Snp" or "Odi".

Category:
Other

Cause:
The Open Tool class name begins with "Snp" or "Odi".

Action:
Ensure the Open Tool class name does not begin with "Snp" or "Odi".

ODI-26071
ODI-26071: Open Tool not activated. Your Open Tool references a class which not found.

Category:
Other

Cause:
The class name specified in this Open Tool was not found.

Action:
Ensure the Open Tool class name specified is valid and available in the class path.

ODI-26072
ODI-26072: Your Open Tool has been installed. You can now use it in a procedure or package.

Category:
Other

Cause:
Installation of the Open Tool has been completed.

Action:
No action is required.

ODI-26073
ODI-26073: Could not activate Open Tool. Check that it is in the "oracledi/userlib" directory.

Category:
Other

Cause:
The Open Tool references a class which was not found.

Action:
Ensure the Open Tool class exists in the "oracledi/userlib" directory.

ODI-26074
ODI-26074: Policy "Name" is a mandatory field.

Category:
Other

Cause:
A value for the Policy "Name" field value was not entered.

Action:
Enter a value for the Policy "Name" field.

ODI-26075
ODI-26075: Policy "Name" must be unique.

Category:
Other

Cause:
A Policy with the same name already exists.

Action:
Enter a unique value in Policy "Name" field.

ODI-26076
ODI-26076: You do not have enough memory to generate this report. Increase the maximum Java heap size value (-Xmx).

Category:
Other

Cause:
There was not enough memory allocated to generate the report.

Action:
Increase the maximum Java heap size value by using the "-Xmx" JVM option.

ODI-26077
ODI-26077: Target file name is not specified.

Category:
Other

Cause:
The Target file name is mandatory and was not specified.

Action:
Enter a value for the target file name.

ODI-26078
ODI-26078: Error while creating the version

Category:
Other

Cause:
An unexpected error occurred while versioning an object.

Action:
Review the error details for further information.

ODI-26079
ODI-26079: Version already exists, versioning aborted.

Category:
Other

Cause:
A version with the specified version number already exists.

Action:
Enter a unique version number.

ODI-26080
ODI-26080: Unable to delete version {0} for {1} {2}. It is referenced by label {3}

Category:
Other

Cause:
Deletion of a version of an object referenced by a Solution was attempted.

Action:
Delete the label referencing the object version. Then retry deleting the object version.

ODI-26081
ODI-26081: Unable to delete version {0} for {1} {2}. It is referenced by version {3} of label {4}

Category:
Other

Cause:
An object version cannot be deleted because it is referenced.

Action:
If an object version must be deleted, remove all references first.

ODI-26082
ODI-26082: No difference found

Category:
Other

Cause:
No difference was found between two object versions.

Action:
No action is required.

ODI-26083
ODI-26083: No difference found.

Category:
Other

Cause:
No difference was found between object versions.

Action:
No action is required.

ODI-26084
ODI-26084: Could not compare versions of different objects.

Category:
Other

Cause:
Objects of different types were selected for comparison.

Action:
Select objects of the same type before performing comparison.

ODI-26085
ODI-26085: You cannot restore several versions of the same object.

Category:
Other

Cause:
Multiple versions were selected for restoring.

Action:
Select a single version when performing this action.

ODI-26086
ODI-26086: You cannot select more than one version at the same time.

Category:
Other

Cause:
Multiple version were selected for this action.

Action:
Select a single version when performing this action.

ODI-26087
ODI-26087: You must select a version.

Category:
Other

Cause:
A version was not selected.

Action:
Select a version before performing this action.

ODI-26088
ODI-26088: You must select the version to restore.

Category:
Other

Cause:
A version to restore was not selected.

Action:
Select a version to restore.

ODI-26089
ODI-26089: This object is currently locked by user: {0}. Version restoration cancelled.

Category:
Other

Cause:
The object selected for restoration was locked by another user.

Action:
Ensure the selected object is not locked by another user before retrying the operation.

ODI-26090
ODI-26090: Object version list is empty.

Category:
Other

Cause:
The object selected was not versioned.

Action:
Select a versioned object before retrying the operation.

ODI-26091
ODI-26091: An array with an invalid size was passed to SnpsObjectTableColumnTextIntrospectMapper.createMapFromArrayOfArrays.

Category:
Other

Cause:
An array with an invalid size was passed to SnpsObjectTableColumnTextIntrospectMapper.createMapFromArrayOfArrays.

Action:
Review the error details for further information.

ODI-26092
ODI-26092: Table Model must have at least one Column.

Category:
Other

Cause:
The Model for this Table did not contain any Columns.

Action:
Add at least one Column to the Table's Model.

ODI-26093
ODI-26093: Unable to open window.

Category:
Other

Cause:
An unexpected error occurred while opening a window.

Action:
Review the error details for further information.

ODI-26094
ODI-26094: Your license does not allow Changed Data Capture operations.

Category:
Other

Cause:
The current license does not include change data capture.

Action:
Upgrade the license to include change data capture.

ODI-26095
ODI-26095: This object is locked by {0}. You cannot edit it unless it is unlocked.

Category:
Other

Cause:
Object could not be opened for write access because it was already locked by another user.

Action:
Ensure the selected object is not locked by another user before retrying the operation.

ODI-26096
ODI-26096: Replacement of object failed.

Category:
Other

Cause:
The file specified did not contain correctly formed XML.

Action:
Ensure the XML in the specified file is valid before retrying the operation.

ODI-26097
ODI-26097: Replace failed due to an SQL exception.

Category:
Other

Cause:
The file used to replace this object is not a valid XML format.

Action:
Select a valid XML file format before performing this replace object action.

ODI-26098
ODI-26098: You must specify an Export Path or File.

Category:
Other

Cause:
Either the Export Path or File was not specified.

Action:
Specify a value for either the Export Path or File.

ODI-26099
ODI-26099: You don't have the appropriate license to use this KM

Category:
Other

Cause:
The current license does not include usage of the specified KM.

Action:
Select another compatible KM or upgrade the license.

ODI-26100
ODI-26100: You don't have the appropriate privileges on Step objects.

Category:
Other

Cause:
Package Steps operation failed due to insufficient ODI security permissions.

Action:
Ensure the ODI user security permissions are correct for the Package Steps object.

ODI-26101
ODI-26101: The Data Check cannot be performed. A CKM is not selected on the Model.

Category:
Other

Cause:
No CKM was assigned to the Model.

Action:
Enter a CKM for the Model before performing the Data Check. Consider using the Model editor to make this entry.

ODI-26102
ODI-26102: The Service cannot be generated. An Application Server is not selected on the Model.

Category:
Other

Cause:
No Application Server was assigned to the Model.

Action:
Enter an Application Server for the Model before performing Generate Service. Consider using the Model editor to make entry.

ODI-26103
ODI-26103: You must specify a connection parameter

Category:
Other

Cause:
Repository connection parameters have not been specified.

Action:
Enter all required repository connection parameters.

ODI-26104
ODI-26104: You must specify a query parameter

Category:
Other

Cause:
A query parameter is missing for retrieving a level.

Action:
Supply the missing parameter.

ODI-26105
ODI-26105: Test failed

Category:
Other

Cause:
The value of Schema, Table, Column or Filter was invalid.

Action:
Ensure the Schema, Table, Column and Filter are valid. Consult the details for additional information.

ODI-26106
ODI-26106: Decryption failed. Data has been restored.

Category:
Other

Cause:
The Decryption process failed.

Action:
Consult the details for additional information.

ODI-26107
ODI-26107: Cannot find this {0} icon

Category:
Other

Cause:
An unexpected error occurred while searching for an icon.

Action:
Review the error details for further information.

ODI-26108
ODI-26108: The specified path is not valid.

Category:
Other

Cause:
The specified path was invalid or was not found on the file system.

Action:
Ensure a valid file system path is entered.

ODI-26109
ODI-26109: Error while reading the search criteria. Invalid file

Category:
Other

Cause:
The selected file did not contain search criteria in a valid format.

Action:
Ensure the selected file is one exported from the ODI search UI and contains correctly formatted search criteria information.

ODI-26110
ODI-26110: An error occurred while saving.

Category:
Other

Cause:
An unexpected error occurred during a save operation.

Action:
Review the error details for further information. Ensure that the repository connection is open.

ODI-26111
ODI-26111: Error while accessing the file

Category:
Other

Cause:
The specified file could not be opened.

Action:
Ensure the specified file exists and is accessible.

ODI-26112
ODI-26112: Error while performing the search

Category:
Other

Cause:
An unexpected error occurred while searching for an object.

Action:
Review the error details for additional information.

ODI-26113
ODI-26113: XML parser configuration error

Category:
Other

Cause:
The selected file is not a valid search criteria file format.

Action:
Select a valid search criteria file exported from the ODI search UI.

ODI-26114
ODI-26114: Host cannot be empty.

Category:
Other

Cause:
The Host field is mandatory and was not specified.

Action:
Enter a valid Host name.

ODI-26115
ODI-26115: Port number must be an integer between 1024 and 65535.

Category:
Other

Cause:
The value for Port Number was not valid.

Action:
Enter a valid integer value between 1024 and 65535 for Port Number.

ODI-26116
ODI-26116: User cannot be empty.

Category:
Other

Cause:
The User field is mandatory and was not supplied.

Action:
Enter a valid User Name.

ODI-26117
ODI-26117: Connection failed. Reason:

Category:
Other

Cause:
Could not connect to a repository with the specified connection details.

Action:
Ensure the repository database is available and valid connection details are supplied.

ODI-26118
ODI-26118: External password storage connection test failed.

Category:
Other

Cause:
Could not connect to the external password storage with the specified connection details.

Action:
Ensure the external password storage is available and valid connection details are supplied.

ODI-26119
ODI-26119: Exception when computing the value

Category:
Other

Cause:
An unexpected error occurred while comparing tables.

Action:
Review the error details for further information.

ODI-26120
ODI-26120: Fields compared are not the same

Category:
Other

Cause:
An unexpected error occurred while comparing fields.

Action:
Review the error details for further information.

ODI-26121
ODI-26121: Error while exploring version

Category:
Other

Cause:
An unexpected error occurred while checking the version.

Action:
Review the error details for further information.

ODI-26122
ODI-26122: Exception when getting the children list

Category:
Other

Cause:
An unexpected error occurred while getting a list of child elements.

Action:
Review the error details for further information.

ODI-26123
ODI-26123: Cannot connect to the repository with the provided login information.

Category:
Other

Cause:
Could not connect to a repository with the specified connection details.

Action:
Ensure the repository database is available and valid connection details are supplied.

ODI-26124
ODI-26124: Exception during connection to the repository with the provided login information:

Category:
Other

Cause:
Could not connect to a repository with the specified connection details.

Action:
Ensure the repository database is available and valid connection details are supplied.

ODI-26125
ODI-26125: The configured external password storage is still accessible. Instead, use the Password Storage Switch service to change the configuration.

Category:
Other

Cause:
Could not connect to the external password storage with the specified connection details.

Action:
Ensure the external password storage is available and valid connection details are supplied. Consider using the Password Storage Switch service to change the configuration.

ODI-26126
ODI-26126: Error while opening window.

Category:
Other

Cause:
An unexpected error occured while opening window.

Action:
Contact Oracle Support Services.

ODI-26127
ODI-26127: The selected master repository configured to use internal password storage. Recovery is possible only for external storages.

Category:
Other

Cause:
Recovery was attempted for a master repository configured to use internal password storage.

Action:
Select a master repository not configured to use internal password storage.

ODI-26128
ODI-26128: Unable to open Editor

Category:
Other

Cause:
An unexpected error occurred while opening an editor.

Action:
Review the error details for further information.

ODI-26129
ODI-26129: Unable to open Editor: Technology could not be opened twice

Category:
Other

Cause:
Technology editor is already open.

Action:
Close the other editor before opening a new technology editor.

ODI-26130
ODI-26130: Could not connect to repository

Category:
Other

Cause:
Could not connect to a repository with the specified connection details.

Action:
Ensure the repository database is available and valid connection details are supplied.

ODI-26131
ODI-26131: Specify Import Path

Category:
Other

Cause:
A value for Import Path is a mandatory and it was not supplied.

Action:
Enter the correct value for the Import Path.

ODI-26132
ODI-26132: Repository id {0} or Repository name {1} is already used in your master repository.

Category:
Other

Cause:
The ID or Name specified for the master repository were already used.

Action:
Enter valid unique values for Repository ID and Repository name.

ODI-26134
ODI-26134: Invalid number format for port number.

Category:
Other

Cause:
The value specified for Port Number was not in a valid format and number range.

Action:
Enter a valid Port Number. See SQL*Net documentation for additional information regarding format and range.

ODI-26135
ODI-26135: The Network Adapter could not establish the connection.

Category:
Other

Cause:
Connection via the Network Adapter could not be established.

Action:
Ensure the network resource is available and the connection details in the Network Adapter are correct..

ODI-26136
ODI-26136: The specified character set is not supported.

Category:
Other

Cause:
The specified character set was not supported.

Action:
Select a supported character set.

ODI-26137
ODI-26137: The context or type are incorrect.

Category:
Other

Cause:
The selected ODI context is invalid: it was probably removed from the repository database.

Action:
Reopen Execution dialog again so that the list of ODI contexts will be reloaded.

ODI-26138
ODI-26138: Server initialization failed.

Category:
Other

Cause:
The attempt to initialize the server failed. This may be due to one or more of the following: invalid connection parameters specified, database problems, network problems.

Action:
Ensure the server is available and acceccesible and the connection parameters are correct.

ODI-26139
ODI-26139: Oozie Engine initialization failed.

Category:
Other

Cause:
The attempt to initialize the Oozie engine failed. This may be due to one or more of the following: invalid connection parameters specified, database problems, network problems.

Action:
Ensure the Oozie engine is available and acceccesible and the connection parameters are correct.

ODI-26140
ODI-26140: Oozie Engine test failed.

Category:
Other

Cause:
The attempt to initialize the Oozie engine failed. This may be due to one or more of the following: invalid connection parameters specified, database problems, network problems.

Action:
Ensure the Oozie engine is available and acceccesible and the connection parameters are correct.

ODI-26150
ODI-26150: Incorrect Context.

Category:
Other

Cause:
A valid Context was not specified.

Action:
Select a Context from the list. If none are available then create one from the Topology Navigator.

ODI-26153
ODI-26153: Connection failed; JDBC Error

Category:
Other

Cause:
An unexpected JDBC error was encountered during the connection process.

Action:
Ensure the resource referenced is available and the connection information is correct.

ODI-26155
ODI-26155: No Master Repository on this connection

Category:
Other

Cause:
A connection to the Master Repository could not be established.

Action:
Ensure the Master Repository is available and valid connection details are provided.

ODI-26156
ODI-26156: Designer cannot connect to an Execution repository. The operation will be canceled.

Category:
Other

Cause:
Unable to establish a connection to the Execution repository.

Action:
Ensure the Execution repository is available and the connection details are correct.

ODI-26157
ODI-26157: Connection Error

Category:
Other

Cause:
A connection to the Master Repository could not be established.

Action:
Ensure the Master Repository is available and valid connection details are provided.

ODI-26158
ODI-26158: Work Repository Attachment Error

Category:
Other

Cause:
A connection to the Work Repository could not be established.

Action:
Ensure the Work Repository is available and valid connection details are provided.

ODI-26159
ODI-26159: Error while creating Work Repository

Category:
Other

Cause:
An unexpected error occurred while creating the Work Repository.

Action:
Correct any issues described in the error details.

ODI-26160
ODI-26160: URL not referenced in the list.

Category:
Other

Cause:
The URL is not valid for the driver.

Action:
Ensure that the URL parameters are correct and in the proper format.

ODI-26161
ODI-26161: File Not Found

Category:
Other

Cause:
The XML file for the driver or URL format list is missing.

Action:
Review the exception for the missing file. Those files should be included with the installation.

ODI-26162
ODI-26162: Connection failure

Category:
Other

Cause:
A connection to the repository could not be established.

Action:
Ensure the repository is available and valid connection details are provided.

ODI-26163
ODI-26163: Access Denied

Category:
Other

Cause:
A connection to the repository could not be established because of insufficient user privilege.

Action:
Ensure the ODI user has sufficient privilege to connect to the specified repository.

ODI-26164
ODI-26164: The reverse cannot be executed. Your Model will be created.

Category:
Other

Cause:
The specified technology or driver did not support standard reverse-engineering.

Action:
Ensure the technology or driver supports standard reverse-engineering. Otherwise choose Customized Reverse and select an appropriate RKM for the technology.

ODI-26165
ODI-26165: This driver has no match in the URL list

Category:
Other

Cause:
A match could not be made between the driver and the list of URLs.

Action:
Ensure that the correct driver has been selected.

ODI-26166
ODI-26166: The template was not generated: {0}

Category:
Other

Cause:
The WLS Template could not be generated.

Action:
Correct any errors identified in the error log and retry the operation.

ODI-26167
ODI-26167: File System Error: {0}

Category:
Other

Cause:
Creation of the Server Template file failed due to an error detected by the file system.

Action:
Correct any errors identified in the error log. Ensure the file system location is accessible and retry the operation.

ODI-26168
ODI-26168: Client requires a repository with version {0} but the repository version found is {1}

Category:
Other

Cause:
Could not connect to the repository due to the old repository version.

Action:
Update repository to the latest version.

ODI-26169
ODI-26169: JDBC driver is mandatory.

Category:
Other

Cause:
JDBC driver was not entered.

Action:
Provide JDBC driver for database connection.

ODI-26170
ODI-26170: JDBC URL is mandatory.

Category:
Other

Cause:
JDBC URL was not entered.

Action:
Provide JDBC URL for database connection.

ODI-26171
ODI-26171: User is mandatory.

Category:
Other

Cause:
User was not entered.

Action:
Provide user for database connection.

ODI-26172
ODI-26172: Id is mandatory.

Category:
Other

Cause:
Id was not entered.

Action:
Provide work repository ID.

ODI-26173
ODI-26173: Name is mandatory.

Category:
Other

Cause:
Name was not entered.

Action:
Provide work repository name.

ODI-26174
ODI-26174: Database connection is not available.

Category:
Other

Cause:
Connection error occurred while connecting to the database.

Action:
Verify that the Database Connection details are correct and the database is available.

ODI-26175
ODI-26175: Import folder does not exist or not a valid folder.

Category:
Other

Cause:
Non-existing or invalid folder was specified.

Action:
Ensure the specified folder path is correct and refers to an existing folder.

ODI-26176
ODI-26176: Import file does not exist or not a valid file.

Category:
Other

Cause:
Non-existing or invalid file was specified.

Action:
Ensure the specified file path is correct and refers to an existing file.

ODI-26177
ODI-26177: Unable to connect to the DBA user.

Category:
Other

Cause:
Unable to connect to the DBA account.

Action:
Check that the DBA username and password are correct.

ODI-26178
ODI-26178: Unable to connect to the Repository user.

Category:
Other

Cause:
Unable to connect to the Repository account.

Action:
Check that the Repository connection details are correct.

ODI-26179
ODI-26179: Invalid Date Format

Category:
Other

Cause:
An Invalid Date format was entered in the date filter.

Action:
Ensure the date entered is of the required format.

ODI-26180
ODI-26180: Changing the name of a sequence only impacts the sequence itself; Users need to manually change object(s) which reference the old sequence name.

Category:
Other

Cause:

Action:

ODI-26181
ODI-26181: Unable to add a Project knowledge module

Category:
Other

Cause:
An unsupported action was attempted.

Action:
No action required as Project knowledge modules are not a valid selection to be added to a solution.

ODI-26182
ODI-26182: Object was modified by another user and cannot be saved.

Category:
Other

Cause:
The object could not be saved. It's possible that the object was modified by another user.

Action:
Try to save changed data, then refresh edited object and apply changed data again.

ODI-26183
ODI-26183: The maximum password length is {0} characters.

Category:
Other

Cause:
The entered work repository password length is greater than allowed.

Action:
Provide a shorter password.

ODI-26184
ODI-26184: SQL error occurred. See error details for more information.

Category:
Other

Cause:
SQL error occurred while performing UI action.

Action:
If this error is not expected, contact Oracle Support Services.

ODI-26185
ODI-26185: File does not exist or cannot be created. See error details for more information.

Category:
Other

Cause:
UI action tried to open a file which did not exist, or create a file which could not be created due to some reasons.

Action:
Make sure the file path is typed correctly. Make sure application has enough file system permissions in order to create a file at the specified path.

ODI-26186
ODI-26186: Character set is not supported. See error details for more information.

Category:
Other

Cause:
UI action tried to use character encoding which is not supported.

Action:
Make sure character set is typed correctly.

ODI-26187
ODI-26187: Unexpected I/O error occurred. See error details for more information.

Category:
Other

Cause:
UI action caused unexpected I/O error.

Action:
Contact Oracle Support Services.

ODI-26188
ODI-26188: There is no enough memory to perform this UI action. Increase the maximum Java heap size value (-Xmx).

Category:
Other

Cause:
UI action requires more memory than available at the current moment.

Action:
Increase the maximum Java heap size value by using the "-Xmx" JVM option.

ODI-26189
ODI-26189: Unexpected report generation error occurred. See error details for more information.

Category:
Other

Cause:
UI action caused unexpected report generation error.

Action:
Contact Oracle Support Services.

ODI-26190
ODI-26190: A user with same name {0} already exists in ODI. Note: LDAP user name is case insensitive. You have to first drop that user prior to registering or changing this one.

Category:
Other

Cause:
Due to LDAP user name is case insensitive so ODI will follow same rule in external authenticaiton mode.

Action:
Please drop the existing user with same name(ingoring case) first prior to registering this one.

ODI-26191
ODI-26191: You cannot move this object because it is locked by another user ({0}).

Category:
Other

Cause:
This object was locked by another user.

Action:
Wait until object is unlocked.

ODI-26192
ODI-26192: You cannot drag & drop this object because it is locked by another user ({0}).

Category:
Other

Cause:
This object was locked by another user.

Action:
Wait until object is unlocked .

ODI-26193
ODI-26193: You are not allowed to delete master repository.

Category:
Other

Cause:
User attempt to delete master repository.

Action:
Cancel deleting master repository.

ODI-26194
ODI-26194: Database Connection User is mandatory.

Category:
Other

Cause:
Database Connection User was not entered.

Action:
Provide Database Connection User.

ODI-26195
ODI-26195: Database Connection Password is mandatory.

Category:
Other

Cause:
Database Connection Password was not entered.

Action:
Provide Database Connection Password.

ODI-26196
ODI-26196: Failed to migrate login information to new format.

Category:
Other

Cause:
ODI was not able to migrate login information from old format into the new format.

Action:
Make sure that directory %ODI_HOME%/oracledi has write permissions. Try manually copying %ODI_HOME%/oracledi/snps_login_work.xml into %ODI_HOME%/oracledi/snps_login_work_12.xml file.

ODI-26197
ODI-26197: Failed to delete old login information.

Category:
Other

Cause:
ODI was not able to delete old login information after migration from old format into the new format.

Action:
Make sure that directory %ODI_HOME%/oracledi and file %ODI_HOME%/oracledi/snps_login_work.xml have write permissions. Try manually removing %ODI_HOME%/oracledi/snps_login_work.xml file.

ODI-26198
ODI-26198: Passwords do not match.

Category:
Other

Cause:
Password confirmation doesn't match the entered password.

Action:
Make sure that password and password confirmation are the same.

ODI-26199
ODI-26199: User {0} is not authorized to grant object {1}.

Category:
Security

Cause:
Current user is not authorized to grant generic object privileges

Action:
Assign generic object privileges to user.

ODI-26200
ODI-26200: User {0} is not authorized to grant method {1}.

Category:
Security

Cause:
Current user is not authorized to grant generic method privileges

Action:
Assign generic method privileges to user.

ODI-26201
ODI-26201: Invalid Export Key. Export Key must have a minimum length of eight characters and maximum length of 100 characters, contain at least one alphabetic (lower/upper case) character, at least one numeric-digit or a special characters (@ # $ % + / =).

Category:
Other

Cause:
Export Key must have a minimum length of eight characters and maximum length of 100 characters, contain at least one alphabetic (lower/upper case) character, at least one numeric-digit or a special characters (@ # $ % + / =).

Action:
Provide a valid Export Key

ODI-26202
ODI-26202: The Export Key and the confirmed Export Key are not the same.

Category:
Other

Cause:
Export Key confirmation doesn't match the entered Export Key.

Action:
Make sure that the Export Key and confirmed Export Key are the same.

ODI-26203
ODI-26203: The provided Export Key is not correct for the selected file.

Category:
Other

Cause:
The provided Export Key is not the same as the Export Key of this selected file.

Action:
Provide a correct Export Key

ODI-26204
ODI-26204: The incorrect Export Key is entered three times. The Export Key field will be disabled now. You can Import this file without an Export Key (the cipher data will not be imported) or Cancel import.

Category:
Other

Cause:
The incorrect Export Key entered 3 times.

Action:
Continue import this file without importing cipher data or Cancel import.

ODI-26205
ODI-26205: The incorrect Export Key is entered three times. The Export Key field will be disabled now. Please consider other options or Cancel import.

Category:
Other

Cause:
The incorrect Export Key entered 3 times.

Action:
Continue import this file or all files without importing cipher data, or Skip the file, or Cancel import.

ODI-26206
ODI-26206: Unable to connect Registry Database to the DBA user.

Category:
Other

Cause:
Unable to connect Registry Database by DBA Account.

Action:
Check Registry Database and the DBA username and password are correct.

ODI-26207
ODI-26207: An Option with the name {0} already exists. Please provide another name.

Category:
Other

Cause:
The name provided for the Option is not unique.

Action:
Enter a unique name for the Option.

ODI-26208
ODI-26208: Unable to perform move because {0} already exists in folder {1}.

Category:
Other

Cause:
A folder already consists a such type of object with the same name as a moving object.

Action:
Rename an object, which you want to move, or rename, or delete an existing object from a folder.

ODI-26209
ODI-26209: Repository Seeding Version Mismatch: A client of an older version is used to connect to a repository that already contains newer map component and KM definitions. Continuing login will not update any seeded objects. Continue login?

Category:
Other

Cause:
A client of an older version is used to connect to a repository that already contains newer map component and KM definitions.

Action:
Update the current client by downloading and installing the latest patch. Insure other clients that connect to the same repository are also at the same patch version.

ODI-26210
ODI-26210: The repository contains map component and KM definitions that are older than the ones supported by the current client version. Clicking Yes will continue the login and the map component definitions will be updated. Clicking No will disconnect from the repository without updating. Do you want to continue?

Category:
Other

Cause:
The current client contains map component and KM definitions that are newer than the ones recorded in the repository.

Action:
Continuing the connection will update the repository with map component and KM definitions at the same version as the client. Check and update other clients that connect to the same repository to the same patch version as the current client.

ODI-26211
Mapping name is not unique.

Category:
Other

Cause:
Duplicate mapping name. Mapping with the same name already exists in this folder.

Action:
Choose another mapping name.

ODI-26212
Reusable mapping name is not unique.

Category:
Other

Cause:
Duplicate reusable mapping name. Reusable mapping with the same name already exists in this folder, or there is another global reusable mapping with the same name.

Action:
Choose another reusable mapping name.

ODI-26213
Cannot create connection from {0} to {1}. Connections can only be made within the same component owner.

Category:
Other

Cause:
Cannot make a connection between two components that are contained in different component owners, for example a connection from a component that is inside a dataset to another component outside the dataset.

Action:
Connect to a component that is contained by the same component owner.

ODI-26214
Cannot find appropriate Knowledge Module for node:{0}

Category:
Programmatic

Cause:
Cannot find a KM to assign to this node.

Action:
Set appropriate KM for physical nodes.

ODI-26215
Error when attempting to set the Loading Knowledge Module to AP node:{0}

Category:
Programmatic

Cause:
Cannot find a LKM to assign to this node.

Action:
Set appropriate LKM for AP nodes.

ODI-26216
Error when attempting to set the Extract Knowledge Module to physical node:{0}

Category:
Programmatic

Cause:
Cannot find a XKM to assign to this node.

Action:
Set appropriate XKM for physical nodes.

ODI-26217
Cannot enable Streaming on Map Physical Design

Category:
Programmatic

Cause:
Map Physical Design does not contain any Execution Unit that supports Streaming

Action:
Set appropriate Streaming value

ODI-26218
Error parsing the data format schema for the {0} attribute: {1}

Category:
Programmatic

Cause:
The data format for the complex type attribute cannot be parsed.

Action:
Correct the data format property for the complex type attribute.

ODI-26219
Data type {0} of complex type field {1} is not a valid HDFS type.

Category:
Programmatic

Cause:
The data type of a field in the complex type attribute is not supported.

Action:
Check the data types used in the data format property for the complex type attribute. Only HDFS types are allowed.

ODI-26220
Complex type attribute {0} for flatten component {1} does not have a data format.

Category:
Programmatic

Cause:
The data format of the complex type attribute cannot be located. The attribute may be a simple type or the data format has not been specified.

Action:
Ensure that the data format of the complex type attribute is set. The format may be specified on a bound data store column or upstream map attribute.

ODI-26221
Complex type attribute {0} for flatten component {1} was not found in any source component.

Category:
Programmatic

Cause:
The complex type attribute cannot be located. The attribute may be spelled incorrectly or may not be in scope in the upstream map components.

Action:
Ensure that the complex type attribute is a valid upstream map attribute.

ODI-26223
Complex data types cannot be used with aggregation. Attribute {0} of aggregate component {1} is a complex type.

Category:
Programmatic

Cause:
Complex type attributes are incompatible with aggregation and grouping. They may not be used with the aggregation component.

Action:
Avoid mapping complex attributes into the aggregate component. The flatten component may be applied to complex types prior to aggregate component mapping.

ODI-26224
Join components may not be used in the same Hive execution unit as flatten components with a complex type with a collection.

Category:
Programmatic

Cause:
Join and Flatten components with a collection are present in the same Hive execution unit. The lateral view clause used for Hive complex type flattening is not compatible with multiple sources in the SQL FROM clause.

Action:
Avoid using flatten components with joins in Hive.

ODI-26300
ODI-26300: Following Flexfields are found missing, which are required to persist this object properly: {0} You can use Security Navigator to define Flexfields for this object type.

Category:
Other

Cause:
There are some required flexfields missing in the editor opened. Without the mentioned flexfields the given object will not persist properly.

Action:
User can use Security Navigator to define Flexfields for this object type.

ODI-26301
ODI-26301: The incorrect Export Key is entered three times. The Export Key field will be disabled now. Please consider other options or cancel the Compare.

Category:
Other

Cause:
The incorrect Export Key entered 3 times.

Action:
Continue comparing this file without cipher data or cancel the Compare.

ODI-26310
ODI-26310: Could not delete the Open Tool {0}. It is used within steps in the following packages: {1}

Category:
Other

Cause:
The Open Tool is used within package steps and cannot be deleted.

Action:
Delete the corresponding steps from the referencing package before deleting the Open Tool.

ODI-30000
Error while parsing request file.

Category:
Files

Cause:

Action:

ODI-30001
One of the following parameters: {0} or {1} must be defined.

Category:
Configuration

Cause:

Action:

ODI-30002
Parameters {0} and {1} cannot be set at the same time.

Category:
Configuration

Cause:

Action:

ODI-30003
OdiOSCommand not supported for this operating system. Use tool "OS Command".

Category:
OperatingSystem

Cause:

Action:

ODI-30004
Agent unreachable

Category:
Network

Cause:

Action:

ODI-30005
One or more child sessions has failed

Category:
Other

Cause:

Action:

ODI-30006
No table matches the specified pattern.

Category:
Other

Cause:

Action:

ODI-30007
No table matches the specified list.

Category:
Other

Cause:

Action:

ODI-30008
No variable with this name is used in the session.

Category:
Other

Cause:

Action:

ODI-30009
Can"t rename file: {0} to {1}

Category:
Files

Cause:

Action:

ODI-30010
Can"t delete old file: {0}

Category:
Files

Cause:

Action:

ODI-30011
Parameter cannot be null:

Category:
Other

Cause:

Action:

ODI-30012
This user does not have the privilege to execute this scenario

Category:
Security

Cause:

Action:

ODI-30013
Context not allowed for this user

Category:
Security

Cause:

Action:

ODI-30014
Cannot create directory

Category:
Files

Cause:

Action:

ODI-30016
Internal error: Invalid datatype

Category:
Other

Cause:

Action:

ODI-30017
Unable to create persistence table

Category:
Other

Cause:

Action:

ODI-30018
Unable to find the tables

Category:
Other

Cause:

Action:

ODI-30019
The Object id is mandatory

Category:
Other

Cause:

Action:

ODI-30020
The command is not valid

Category:
Other

Cause:

Action:

ODI-30021
Value 0 is not allowed for -GLOBAL_ROWCOUNT.

Category:
Other

Cause:

Action:

ODI-30022
Version is mandatory ...

Category:
Other

Cause:

Action:

ODI-30023
Scenario name is mandatory ...

Category:
Other

Cause:

Action:

ODI-30024
File name is mandatory...

Category:
Other

Cause:

Action:

ODI-30025
Agent name is mandatory ...

Category:
Other

Cause:

Action:

ODI-30026
Either the "{0}" or the "{1}" parameter is mandatory ...

Category:
Other

Cause:

Action:

ODI-30027
The parameter -LSCHEMA is mandatory.

Category:
Other

Cause:

Action:

ODI-30028
The parameter -SUBSCRIBER_NAME is mandatory.

Category:
Other

Cause:

Action:

ODI-30029
Parameter -RESUME_KEY_COL is mandatory when -RESUME_KEY_VAR is used

Category:
Other

Cause:

Action:

ODI-30030
Please do not pass values for both "{0}" and "{1}" options together. These two options together are not supported

Category:
Other

Cause:

Action:

ODI-30031
The parameter "{0}" is mandatory.

Category:
Other

Cause:

Action:

ODI-30032
Unrecognized ODI object type "{0}". Please check the value passed to the parameter "{1}".

Category:
Other

Cause:

Action:

ODI-30033
The parameter "-CONTEXT" is mandatory when running from command line.

Category:
Other

Cause:

Action:

ODI-30034
Only positive integer values are valid for {0} parameter

Category:
Other

Cause:

Action:

ODI-30035
Only non-negative integer values are valid for {0} parameter

Category:
Other

Cause:

Action:

ODI-30036
This step cannot be executed in execution work repository because the model meta data does not exist

Category:
Other

Cause:

Action:

ODI-30037
The specified marker does not exist

Category:
Other

Cause:

Action:

ODI-30038
OS command returned {0}. Error details are [{1}].

Category:
Other

Cause:

Action:

ODI-30039
Parameter -RESUME_KEY_VAR is mandatory when -RESUME_KEY_COL is used

Category:
Other

Cause:

Action:

ODI-30040
The -TABLE_NAME parameter is mandatory.

Category:
Other

Cause:

Action:

ODI-30041
LSCHEMA parameter is mandatory

Category:
Other

Cause:

Action:

ODI-30042
SUBSCRIBER_NAME parameter is mandatory

Category:
Other

Cause:

Action:

ODI-30043
You cannot use the OPTIMIZED_WAIT option with the current journalizing method.

Category:
Other

Cause:

Action:

ODI-30044
Invalid parameter

Category:
Other

Cause:

Action:

ODI-30045
Impossible to find a valid name on this machine for the "{0}" file

Category:
Other

Cause:

Action:

ODI-30046
Session stopped

Category:
Other

Cause:

Action:

ODI-30047
You cannot select more than one source.

Category:
Other

Cause:

Action:

ODI-30048
Unable to find the object with type {0} and identifier {1}

Category:
Other

Cause:

Action:

ODI-30049
Version is mandatory ...

Category:
Other

Cause:

Action:

ODI-30050
The same file cannot be used as the source and the target.

Category:
Files

Cause:

Action:

ODI-30051
File does not exist.

Category:
Files

Cause:

Action:

ODI-30052
No file found.

Category:
Files

Cause:

Action:

ODI-30053
File name is mandatory ...

Category:
Files

Cause:

Action:

ODI-30054
It is not possible to delete sessions in the queue.

Category:
Other

Cause:

Action:

ODI-30055
Context is mandatory ...

Category:
Other

Cause:

Action:

ODI-30056
Sequence name is mandatory

Category:
Other

Cause:

Action:

ODI-30057
The position is a mandatory parameter.

Category:
Other

Cause:

Action:

ODI-30058
-SCEN_NAME parameter is mandatory.

Category:
Other

Cause:

Action:

ODI-30059
The number of child sessions in error state is greater or equal to the MAX_CHILD_ERROR parameter

Category:
Other

Cause:

Action:

ODI-30060
The parent session "{0}" does not exist.

Category:
Other

Cause:

Action:

ODI-30061
"{0}" is not a correct value for -OBJECT_TYPE

Category:
Other

Cause:

Action:

ODI-30062
There's no table matching the pattern in the database

Category:
Other

Cause:

Action:

ODI-30063
-TABLE_NAME and -CDC_SET_NAME cannot be used simultaneously.

Category:
Other

Cause:

Action:

ODI-30064
You must specify -TABLE_NAME or -CDC_SET_NAME

Category:
Other

Cause:

Action:

ODI-30065
Incorrect length at position :{0} for value : {1} expected max size of {2}

Category:
Other

Cause:

Action:

ODI-30066
All child sessions have failed

Category:
Other

Cause:

Action:

ODI-30067
-UNIT_ROW_COUNT and -CDC_SET_NAME cannot be used simultaneously.

Category:
Other

Cause:

Action:

ODI-30068
Unable to find the table(s): {0}

Category:
Other

Cause:

Action:

ODI-30069
You must specify a Project

Category:
Other

Cause:

Action:

ODI-30070
You have not specified the export scenarios location.

Category:
Other

Cause:

Action:

ODI-30071
You have not specified the export location.

Category:
Other

Cause:

Action:

ODI-30072
Unable to delete a running session

Category:
Other

Cause:

Action:

ODI-30073
Unable to delete a waiting session

Category:
Other

Cause:

Action:

ODI-30074
{0}: Illegal value

Category:
Other

Cause:

Action:

ODI-30075
Cannot be specified at the same time: {0} and {1}

Category:
Other

Cause:

Action:

ODI-30076
Unable to save the line number sum

Category:
Other

Cause:

Action:

ODI-30077
The variable in use is null.

Category:
Other

Cause:

Action:

ODI-30078
No message.

Category:
Other

Cause:

Action:

ODI-30079
Mandatory Parameter "{0}" is missing

Category:
Other

Cause:

Action:

ODI-30080
Cannot copy a directory "{0}" to a regular file "{1}"

Category:
Files

Cause:

Action:

ODI-30081
The source directory file "{0}" does not exist

Category:
Files

Cause:

Action:

ODI-30082
The source directory file "{0}" is not a directory

Category:
Files

Cause:

Action:

ODI-30083
Invalid value "{0}" passed for parameter "{1}"

Category:
Other

Cause:

Action:

ODI-30084
File "{0}" does not exist

Category:
Files

Cause:

Action:

ODI-30085
Cannot copy file with a regular expression to a regular file "{0}"

Category:
Files

Cause:

Action:

ODI-30086
The FROMDATE {0} should be earlier than the TODATE {1}

Category:
Other

Cause:

Action:

ODI-30087
Import failed. No work repository name was defined and the import failed in the master repository.

Category:
Other

Cause:

Action:

ODI-30088
Timed out. No result.

Category:
Other

Cause:

Action:

ODI-30089
Source file "{0}" does not exist

Category:
Files

Cause:

Action:

ODI-30090
Scenario name is mandatory ...

Category:
Other

Cause:

Action:

ODI-30091
Invalid internal object transition

Category:
Other

Cause:

Action:

ODI-30092
Cannot create directory

Category:
Files

Cause:

Action:

ODI-30093
PORT and NAME parameters can"t be used together.

Category:
Other

Cause:

Action:

ODI-30094
Log files can only be imported in synonym mode INSERT.

Category:
Other

Cause:
The value of parameter -IMPORT_MODE is invalid for this type of object.

Action:
Modify the value of parameter -IMPORT_MODE to SYNONYM_INSERT

ODI-30095
PROMPT option can only be used when ReverseManageShortcut tool is run from ODI UI and on a Local Agent.

Category:
Other

Cause:
The value of parameter -SHORTCUT_HANDLING_MODE is invalid for this mode of execution.

Action:
Modify the value of parameter -SHORTCUT_HANDLING_MODE to ALWAYS_MATERIALIZE or ALWAYS_SKIP

ODI-30096
Invalid shortcut handling mode.

Category:
Other

Cause:
The value of parameter -SHORTCUT_HANDLING_MODE is invalid.

Action:
Modify the value of parameter -SHORTCUT_HANDLING_MODE to ALWAYS_MATERIALIZE or ALWAYS_SKIP or PROMPT.

ODI-30097
-LOCATION parameter is mandatory.

Category:
Other

Cause:

Action:

ODI-30098
-OBJECT_NAME parameter is mandatory.

Category:
Other

Cause:

Action:

ODI-30099
-OBJECT_TYPE parameter is mandatory.

Category:
Other

Cause:

Action:

ODI-30100
-WORKSPACE parameter is mandatory.

Category:
Other

Cause:

Action:

ODI-30101
Enterprise Data Quality project {0} not found.

Category:
Other

Cause:

Action:

ODI-30102
Enterprise Data Quality Job {0} not found in Enterprise Data Quality project {1}.

Category:
Other

Cause:

Action:

ODI-30103
Enterprise Data Quality matching query returned with empty or ambiguous result for {0}.

Category:
Other

Cause:

Action:

ODI-30104
Model Internal ID is not supported when Legacy ID Compatible Mode is switched off.

Category:
Other

Cause:

Action:

ODI-30105
Internal ID is not supported for "{0}" when Legacy ID Compatible Mode is switched off. Only Global ID is supported.

Category:
Other

Cause:

Action:

ODI-30106
JAX-WS Dispatch proxy object could not be created. Check ODI Agent log for error messages.

Category:
Other

Cause:

Action:

ODI-30107
Upgrade key is required for pre-12.x object import.

Category:
Other

Cause:

Action:

ODI-30108
Target directory "{0}" does not exist

Category:
Files

Cause:

Action:

ODI-30109
Error while polling run status of load plan {0} (instance id {1}, run {2}) for execution completion. Last polled status value: {3}.

Category:
Other

Cause:

Action:

ODI-30110
Execution of load plan {0} (instance id {1}, run {2}) ended in status "{3}" instead of "{4}". {5}

Category:
Other

Cause:

Action:

ODI-30111
Value for mandatory parameter {0} is missing.

Category:
Other

Cause:

Action:

ODI-30112
Invalid logical schema "{0}" selected for PROCESS_LSCHEMA parameter. Oracle Golden Gate process logical schema is expected.

Category:
Other

Cause:

Action:

ODI-30113
Values for mandatory parameters PROCESS_LSCHEMA and OPERATION are missing.

Category:
Other

Cause:

Action:

ODI-30114
Oracle GoldenGate process logical schema with the name {0} does not exist.

Category:
Other

Cause:

Action:

ODI-30115
All selected load plan runs ({0}) have completed, with {1} in Error status.

Category:
Other

Cause:

Action:

ODI-30116
The number of load plan runs in error status ({0} in error out of {1} completed runs), is at or above the MAX_LP_ERROR limit of {2}.

Category:
Other

Cause:

Action:

ODI-30117
The parent session "{0}" does not exist.

Category:
Other

Cause:

Action:

ODI-30118
The value "{0}" specified for the -NB_PROCESS parameter is invalid. A valid value must be a positive integer.

Category:
Other

Cause:

Action:

ODI-30119
Error while splitting XML file. Target file {0} already exists.

Category:
Other

Cause:

Action:

ODI-30120
Authentication mechanisms (parameter: AUTHMECHANISMS) is required when Use Authentication (parameter: AUTH) is set to Yes.

Category:
Other

Cause:

Action:

ODI-30121
This operation {0} is not to be invoked

Category:
Other

Cause:

Action:

ODI-30122
Error while writing output XML file - {0}.

Category:
Other

Cause:

Action:

ODI-30124
Error while parsing input XML file - {0}.

Category:
Other

Cause:

Action:

ODI-30125
Error while creating SystemID using the XML file input - {0}.

Category:
Other

Cause:

Action:

ODI-30126
Error on parsing header.

Category:
Other

Cause:

Action:

ODI-30127
Error on parsing footer.

Category:
Other

Cause:

Action:

ODI-30128
Error while joining XML files.

Category:
Other

Cause:

Action:

ODI-30129
The user {0} does not have privileges to export Scenario {1} ({2})

Category:
Other

Cause:

Action:

ODI-30130
The user {0} does not have privileges to import a Scenario.

Category:
Other

Cause:

Action:

ODI-30131
The user {0} does not have privileges to generate a Scenario.

Category:
Other

Cause:

Action:

ODI-30132
The user {0} does not have privileges to export Scenarios.

Category:
Other

Cause:

Action:

ODI-30133
Specified folder with ID {0} does not exist in repository.

Category:
Other

Cause:

Action:

ODI-30134
Specified scenario {0} of version {1} does not exist in repository.

Category:
Other

Cause:

Action:

ODI-30135
Invalid arguments for OdiExportObject tool. EXPORT_DIR="{0}",FILE_NAME="{1}". When EXPORT_DIR value is not specified, FILE_NAME value must contain absolute path.

Category:
Other

Cause:

Action:

ODI-30136
Incorrect EDQ server domain name {0}.

Category:
Other

Cause:

Action:

ODI-30137
Invalid arguments for OdiExportAllScen when connected to Runtime Repository. Design repository parameters cannot be used on runtime repository.

Category:
Other

Cause:

Action:

ODI-30138
Invalid Source type provided. Valid Source types for OdiCreateDeploymentArchive are ODI or VCS.

Category:
Other

Cause:

Action:

ODI-30139
Invalid Archive type provided. Valid Archive type for Source type ODI is INITIAL.

Category:
Other

Cause:

Action:

ODI-30140
VCS Label not provided for Source VCS.

Category:
Other

Cause:

Action:

ODI-30141
Invalid VCS type provided. Valid VCS type is SVN.

Category:
Other

Cause:

Action:

ODI-30142
Invalid VCS Authentication type provided. Valid values are SVNBASIC|BASIC|PROXY|SSH|SSL|FILE.

Category:
Other

Cause:

Action:

ODI-30143
VCS URL not provided.

Category:
Other

Cause:

Action:

ODI-30144
VCS User name is mandatory for authentication type {0}.

Category:
Other

Cause:

Action:

ODI-30145
VCS Password is mandatory for authentication type {0}.

Category:
Other

Cause:

Action:

ODI-30146
Proxy Host as well as Proxy port are mandatory for authentication type {0}.

Category:
Other

Cause:

Action:

ODI-30147
Invalid Archive type provided. Valid Archive types for OdiApplyDeploymentArchive are INITIAL or PATCH.

Category:
Other

Cause:

Action:

ODI-30148
Invalid Archive type provided. Valid Archive type for OdiRollbackDeploymentArchive is ROLLBACK.

Category:
Other

Cause:

Action:

ODI-30149
The timeout was reached before all of the sessions could be retrieved.

Category:
Other

Cause:

Action:

ODI-30150
Current user is not VCS ADMIN to perform unlock operation

Category:
Other

Cause:

Action:

ODI-30151
Error while setting parameters on tool: {0}

Category:
Other

Cause:

Action:

ODI-30152
Archive Name needs to be provided.

Category:
Other

Cause:

Action:

ODI-30153
Export Key is required when Create without cipher data option is selected as No.

Category:
Other

Cause:

Action:

ODI-30154
Parameter {0} cannot be null, when -LSCHEMA is null. Either -LSCHEMA or (all of -HOST,-PORT,-USER,-PASSWORD,-DOMAIN) are mandatory and cannot be null.

Category:
Other

Cause:

Action:

ODI-30155
SSH Port is mandatory for authentication type {0}.

Category:
Other

Cause:

Action:

ODI-30156
Neither VCS Password nor Private Key file details provided for SSH.

Category:
Other

Cause:

Action:

ODI-30157
---------- Environment Variables Defined By OSCommand -ENV.* Parameters ----------

Category:
Other

Cause:

Action:

ODI-30158
---------- Environment Variables Used By OSCommand ----------

Category:
Other

Cause:

Action:

ODI-30159
Parameters {0} and {1} cannot be set at the same time.

Category:
Configuration

Cause:

Action:

ODI-30160
Incomplete multipart parameters.

Category:
Configuration

Cause:

Action:

ODI-30161
Invalid content type specified for multipart request.

Category:
Configuration

Cause:

Action:

ODI-30162
Non-numeric value specified for numeric parameter : {0}

Category:
Configuration

Cause:

Action:

ODI-30163
REST tool invocation failed with response code : {0}. URL : {1}

Category:
Other

Cause:

Action:

ODI-30164
Rest invocation failed with error. URL : {0}

Category:
Other

Cause:

Action:

ODI-30165
Unable to read file from HDFS path : {0}

Category:
Other

Cause:

Action:

ODI-30166
Error while reading the content of body part file : {0}

Category:
Other

Cause:

Action:

ODI-30167
Error accessing trace file. Trace file path : {0}

Category:
Other

Cause:

Action:

ODI-30168
Error accessing response file. Response file path : {0}

Category:
Other

Cause:

Action:

ODI-30169
Response status generation failed. File path : {0}

Category:
Other

Cause:

Action:

ODI-30170
Multipart bodypart creation failed.

Category:
Other

Cause:

Action:

ODI-30171
No response file specified for mode : {0}

Category:
Configuration

Cause:

Action:

ODI-30172
Invalid operation : {0}

Category:
Configuration

Cause:

Action:

ODI-30173
Unable to resolve physical schema due to invalid LSchema/Context pair : {0}/{1}

Category:
Configuration

Cause:

Action:

ODI-30174
WaitForSparkJob getStatus request failed : url={0} exception={1}

Category:
Other

Cause:

Action:

ODI-30175
WaitForSparkJob getStatus bad response code : expected={0} received={1} url={2}

Category:
Other

Cause:

Action:

ODI-30176
WaitForSparkJob getStatus response not compatible : expected={0} received={1} url={2}

Category:
Other

Cause:

Action:

ODI-30177
WaitForSparkJob killJob request failed : url={0} exception={1}

Category:
Other

Cause:

Action:

ODI-30178
WaitForSparkJob killJob bad response code : expected={0} received={1} url={2}

Category:
Other

Cause:

Action:

ODI-30179
WaitForSparkJob killJob response not compatible : expected={0} received={1} url={2}

Category:
Other

Cause:

Action:

ODI-30180
WaitForSparkJob killJob : stop requested but -STOP_URL not specifed url={0}

Category:
Other

Cause:

Action:

ODI-30181
Error Obtaining data schema for the given Logical Schema={0}

Category:
Files

Cause:

Action:

ODI-30182
WaitForSparkJob url : {0} redirected to {1}

Category:
Other

Cause:

Action:

ODI-30183
Unable to connect to REST service after {0} retry attempts. REST URL : {1}

Category:
Other

Cause:

Action:

ODI-30184
Unable to resolve next request. Resolver class used : {0}

Category:
Other

Cause:

Action:

ODI-30185
Invalid next request resolver provided. Next request resolver : {0} Resolver Class : {1}

Category:
Configuration

Cause:

Action:

ODI-30186
Invalid rest request object modification by next page resolver : {1}. Rest request object should contain request path

Category:
Other

Cause:

Action:

ODI-30187
Invocation retry interrupted with {0} attempts left. REST URL : {1}

Category:
Other

Cause:

Action:

ODI-30188
Unable to retrieve value for tool parameter : {0}

Category:
Other

Cause:

Action:

ODI-30189
Invalid value "{0}" provided for tool parameter : {1}

Category:
Configuration

Cause:

Action:

ODI-30190
Error while copying temp response file to original response file

Category:
Other

Cause:

Action:

ODI-30191
Invalid ResponseDataContainerResolver expression : {0}. It should be either Xpath nor JSONPath expression

Category:
Configuration

Cause:

Action:

ODI-30192
Invalid Resolver Overwrite class : {0}

Category:
Configuration

Cause:

Action:

ODI-30193
No value provided for request body part

Category:
Configuration

Cause:

Action:

ODI-30194
No body provided for request body part. Please provide either body part value or body part input stream.

Category:
Configuration

Cause:

Action:

ODI-30195
-REQUEST_BODY_FILE parameter is mandatory for Chunk Upload. User should specify a directory or file path in local file system or HDFS file system

Category:
Configuration

Cause:

Action:

ODI-30196
Invalid Runtime Template set by the user : {0}

Category:
Configuration

Cause:

Action:

ODI-30197
Offsetbased pagination will not terminate due to invalid -NEXT_REQUEST_RESOLVER : {0}

Category:
Configuration

Cause:

Action:

ODI-30198
A runtime template : {0} is found to be initialized in the tool parameter. Runtime templates should be initialized only while defining the operation.

Category:
Configuration

Cause:

Action:

ODI-30199
A value has been set to runtime template "{0}". But the runtime template is not used in the REST invocation. Please check if you have missed to specify it in either path,query or header.

Category:
Configuration

Cause:

Action:

ODI-30200
Source Logical schema not provided.

Category:
Other

Cause:

Action:

ODI-30201
Target Logical schema not provided.

Category:
Other

Cause:

Action:

ODI-30202
File names filter not provided.

Category:
Other

Cause:

Action:

ODI-30203
Retry on error is greater than 0 and retry interval seconds is null or empty.

Category:
Other

Cause:

Action:

ODI-30204
Encrypt is true and encrypt key is null or empty.

Category:
Other

Cause:

Action:

ODI-30205
Encrypt is not applicable for storage type ARCHIVE.

Category:
Other

Cause:

Action:

ODI-30206
Storage type is invalid.

Category:
Other

Cause:

Action:

ODI-30207
Source Logical schema not provided.

Category:
Other

Cause:

Action:

ODI-30208
Target Logical schema not provided.

Category:
Other

Cause:

Action:

ODI-30209
File names filter not provided.

Category:
Other

Cause:

Action:

ODI-30211
No matching files to {0}. Check your filter string.

Category:
Other

Cause:

Action:

ODI-30212
The value: {0} specified for the parameter: {1} is invalid. A valid value must be a positive integer.

Category:
Other

Cause:

Action:

ODI-30213
VCS Lock type is invalid.

Category:
Other

Cause:

Action:

ODI-30214
Invalid VCS type provided.

Category:
Other

Cause:

Action:

ODI-30215
Invalid VCS Authentication type provided. Valid values are SVNBASIC|BASIC|PROXY|SSH|SSL|FILE.

Category:
Other

Cause:

Action:

ODI-30216
VCS URL is not provided.

Category:
Other

Cause:

Action:

ODI-30217
VCS User name is mandatory for authentication type {0}.

Category:
Other

Cause:

Action:

ODI-30218
VCS Password is mandatory for authentication type {0}.

Category:
Other

Cause:

Action:

ODI-30219
Proxy Host as well as Proxy port are mandatory for authentication type {0}.

Category:
Other

Cause:

Action:

ODI-30220
SSH Port is mandatory for authentication type {0}.

Category:
Other

Cause:

Action:

ODI-30221
Neither VCS Password nor Private Key file details provided for SSH..

Category:
Other

Cause:

Action:

ODI-30222
Provided Password is not encrypted for parameter : {0}.

Category:
Other

Cause:

Action:

ODI-30223
Git Repository is not cloned, Please clone from remote Git repository.

Category:
Other

Cause:

Action:

ODI-30224
No matching files to {0}. Check your filter string.

Category:
Other

Cause:

Action:

ODI-30225
Storage type not provided.

Category:
Other

Cause:

Action:

ODI-30226
Provided key is not encrypted for parameter : {0}.

Category:
Other

Cause:

Action:

ODI-30227
Rest invocation failed with error : {0}. Response code : {1}. URL : {2}

Category:
Other

Cause:

Action:

ODI-40001
Cannot join two journalized sets of data: {0} and {1}.

Category:
Programmatic

Cause:
The generated query object has detected multiple journalized data sources, only one is allowed.

Action:
Switch off journalizing for one of the sources, in the logical or physical graph.

ODI-40100
Invalid JDBC URL {0} . No XSD or DTD was provided.

Category:
Configuration

Cause:

Action:

ODI-40101
Not Supported

Category:
Other

Cause:

Action:

ODI-40102
The parameter {0} has already been specified for {1}.

Category:
Other

Cause:

Action:

ODI-40103
No value provided for JMS_DESTINATION

Category:
Other

Cause:

Action:

ODI-40104
The URL {0} does not start with {1}

Category:
Other

Cause:

Action:

ODI-40105
Connecting to JMS using URL {0} failed

Category:
Other

Cause:

Action:

ODI-40106
JNDI protocol not specified after the JMS XML protocol prefix : {0}

Category:
Other

Cause:

Action:

ODI-40107
Path separator ":" after JNDI protocol not found {0}

Category:
Other

Cause:

Action:

ODI-40108
"//" after colon not found : {0}

Category:
Other

Cause:

Action:

ODI-40109
Need more information than JNDI hostname. eg: port, provider : {0}

Category:
Other

Cause:

Action:

ODI-40110
Could not find JNDI host, port, provider info : {0}

Category:
Other

Cause:

Action:

ODI-40111
Error closing JMS XML connection

Category:
Other

Cause:

Action:

ODI-40200
Cannot create the initial JNDI context. Check that the JNDI server is running, and that the following URL is correct ({0}).

Category:
Other

Cause:

Action:

ODI-40201
Cannot create the initial JNDI context

Category:
Other

Cause:

Action:

ODI-40202
Cannot find the target in JNDI ({0})

Category:
Other

Cause:

Action:

ODI-40203
Cannot find the Connection Factory ({0}) in JNDI

Category:
Other

Cause:

Action:

ODI-40204
The URL cannot be null

Category:
Network

Cause:

Action:

ODI-40205
No connection.

Category:
Network

Cause:

Action:

ODI-40206
Problem with getInternalSession

Category:
Other

Cause:

Action:

ODI-40207
You must specify the URL parameter

Category:
Configuration

Cause:

Action:

ODI-40208
This function has no effect for this connection

Category:
Other

Cause:

Action:

ODI-40209
Unable to create the table

Category:
Other

Cause:

Action:

ODI-40210
Unable to drop the table

Category:
Other

Cause:

Action:

ODI-40212
Missing file structure in the request

Category:
Other

Cause:

Action:

ODI-40213
Error performing update

Category:
Other

Cause:

Action:

ODI-40214
Error creating prepared statement

Category:
Other

Cause:

Action:

ODI-40215
Error performing commit

Category:
Other

Cause:

Action:

ODI-40216
Error performing update

Category:
Other

Cause:

Action:

ODI-40217
Error closing resultset

Category:
Other

Cause:

Action:

ODI-40218
Error getting next element in resultset

Category:
Other

Cause:

Action:

ODI-40219
Error opening file for insert

Category:
Other

Cause:

Action:

ODI-40220
Error creating prepared statement

Category:
Other

Cause:

Action:

ODI-40221
Error writing

Category:
Other

Cause:

Action:

ODI-40222
Error initializing

Category:
Other

Cause:

Action:

ODI-40223
Error performing commit

Category:
Other

Cause:

Action:

ODI-40224
Error obtaining connection

Category:
Other

Cause:

Action:

ODI-40225
Error performing rollback

Category:
Other

Cause:

Action:

ODI-40226
Error initializing

Category:
Other

Cause:

Action:

ODI-40227
Error performing commit

Category:
Other

Cause:

Action:

ODI-40228
Error obtaining connection

Category:
Other

Cause:

Action:

ODI-40229
Error performing rollback

Category:
Other

Cause:

Action:

ODI-40230
Error closing JMS

Category:
Other

Cause:

Action:

ODI-40231
Error closing JNDI

Category:
Other

Cause:

Action:

ODI-40232
Error closing JNDI

Category:
Other

Cause:

Action:

ODI-40233
Error closing JNDI

Category:
Other

Cause:

Action:

ODI-40234
Error writing received message to temp file

Category:
Other

Cause:

Action:

ODI-40300
File is read-only.

Category:
Files

Cause:

Action:

ODI-40301
Invalid COL ALIAS "{0}" for column "{1}"

Category:
Other

Cause:

Action:

ODI-40302
Invalid format description

Category:
Files

Cause:

Action:

ODI-40303
XML/LDAP driver encountered exception during decryption of password for DB connection

Category:
Other

Cause:

Action:

ODI-40304
The URL can not be null.

Category:
Other

Cause:

Action:

ODI-40305
Invalid property "{0}"

Category:
Other

Cause:

Action:

ODI-40306
Property {0} has invalid value {1}

Category:
Other

Cause:

Action:

ODI-40307
Parameter "{0}" has been declared twice. Old value : "{1}" New value : "{2}"

Category:
Other

Cause:

Action:

ODI-40400
Invalid format description

Category:
Files

Cause:

Action:

ODI-40401
Mis-matched start/end delimiters

Category:
Files

Cause:

Action:

ODI-40402
File metadata could not be obtained for {0}

Category:
Files

Cause:

Action:

ODI-40403
Unable to obtain row structure for file {0}

Category:
Files

Cause:

Action:

ODI-40404
Array must not be null

Category:
Other

Cause:

Action:

ODI-40405
End must be greater than begin: {0} > {1}

Category:
Other

Cause:

Action:

ODI-40406
Bytes are too big for array

Category:
Other

Cause:

Action:

ODI-40407
Begin interval must be >= 0: {0}

Category:
Other

Cause:

Action:

ODI-40408
End interval must not go beyond the size of the pointed array: {0}

Category:
Other

Cause:

Action:

ODI-40409
Array must not be null

Category:
Other

Cause:

Action:

ODI-40410
End must be greater than begin: {0} > {1}

Category:
Other

Cause:

Action:

ODI-40411
Begin interval must be >= 0: {0}

Category:
Other

Cause:

Action:

ODI-40412
End interval must not go beyond the size of the pointed array: {0}

Category:
Other

Cause:

Action:

ODI-40413
Bytes are too long for array

Category:
Files

Cause:

Action:

ODI-40414
Reader has been closed

Category:
Files

Cause:

Action:

ODI-40415
File {0} already exists

Category:
Files

Cause:

Action:

ODI-40416
Could not create file {0}

Category:
Files

Cause:

Action:

ODI-40417
An IOException was caught while creating the file saying {0}

Category:
Files

Cause:

Action:

ODI-40418
File not found: {0}

Category:
Files

Cause:

Action:

ODI-40419
Could not delete file: {0}

Category:
Files

Cause:

Action:

ODI-40420
Bad String size, hex Strings should have an even size

Category:
Other

Cause:

Action:

ODI-40421
Cannot code String {0} into {1} bytes using the encoding {2}.

Category:
Other

Cause:

Action:

ODI-40422
The array of bytes is not a valid number:

Category:
Other

Cause:

Action:

ODI-40423
A bad number was found in a COMP3 format: {0} at position {1}

Category:
Other

Cause:

Action:

ODI-40424
Cannot code value {0} on {1} bytes.

Category:
Other

Cause:

Action:

ODI-40425
Bad number in a ZONED format: {0} at position {1}

Category:
Other

Cause:

Action:

ODI-40426
URL must start with {0}

Category:
Other

Cause:

Action:

ODI-40427
Unknown property: {0}

Category:
Other

Cause:

Action:

ODI-40428
Could not write header rows to file: {0}

Category:
Files

Cause:

Action:

ODI-40429
An IOException occured while writing a row saying: {0}

Category:
Other

Cause:

Action:

ODI-40430
Unknown property

Category:
Other

Cause:

Action:

ODI-40431
Could not close output file

Category:
Files

Cause:

Action:

ODI-40432
File {0} is read-only

Category:
Files

Cause:

Action:

ODI-40433
File {0} was not found

Category:
Other

Cause:

Action:

ODI-40434
Could not clone a row of type {0}

Category:
Other

Cause:

Action:

ODI-40435
Could not transform data for column {0} value {1} because: {2}

Category:
Other

Cause:

Action:

ODI-40436
JVM 1.4 at least is required

Category:
Compliance

Cause:

Action:

ODI-40437
Number of bad rows actually detected: {0}

Category:
Other

Cause:

Action:

ODI-40438
File not found: {0}

Category:
Files

Cause:

Action:

ODI-40439
Could not read heading rows from file

Category:
Other

Cause:

Action:

ODI-40440
Could not close file: {0}

Category:
Other

Cause:

Action:

ODI-40441
Error reading file: {0} said {1}

Category:
Other

Cause:

Action:

ODI-40442
Could not translate value for column {0}

Category:
Other

Cause:

Action:

ODI-40443
Could not convert value of type {0} to BigDecimal

Category:
Other

Cause:

Action:

ODI-40444
Column not found: {0}

Category:
Other

Cause:

Action:

ODI-40445
Column {0} > {1}.

Category:
Other

Cause:

Action:

ODI-40446
Column {0} negative or zero.

Category:
Other

Cause:

Action:

ODI-40447
This type is not valid datatype

Category:
Other

Cause:

Action:

ODI-40448
File is read-only.

Category:
Files

Cause:

Action:

ODI-40449
File not found: {0}

Category:
Files

Cause:

Action:

ODI-40450
An IOException occured saying: {0}

Category:
Files

Cause:

Action:

ODI-40451
Column Not Found:

Category:
Other

Cause:

Action:

ODI-40452
Missing file structure in the request

Category:
Files

Cause:

Action:

ODI-40453
Missing JMS properties in the request

Category:
Other

Cause:

Action:

ODI-40454
Missing host variable at index

Category:
Other

Cause:

Action:

ODI-40455
Not a numeric value

Category:
Other

Cause:

Action:

ODI-40456
A Number datatype was expected instead of :

Category:
Other

Cause:

Action:

ODI-40457
Parsing error

Category:
Other

Cause:

Action:

ODI-40458
Unknown column datatype

Category:
Other

Cause:

Action:

ODI-40459
An IOException occurred saying {0}

Category:
Files

Cause:

Action:

ODI-40460
Could not transform the data: {0}

Category:
Other

Cause:

Action:

ODI-40461
A Date datatype was expected instead of :

Category:
Other

Cause:

Action:

ODI-40462
File already exists

Category:
Files

Cause:

Action:

ODI-40463
Invalid cursor state

Category:
Other

Cause:

Action:

ODI-40464
Invalid descriptor index

Category:
Other

Cause:

Action:

ODI-40465
Data array must not be null

Category:
Other

Cause:

Action:

ODI-40466
String is too long: {0}

Category:
Other

Cause:

Action:

ODI-40467
Too many columns on this row

Category:
Other

Cause:

Action:

ODI-40468
Row rejected because column {0} contains a bad value.

Category:
Other

Cause:

Action:

ODI-40469
Value was incorrect for column {0}: {1}

Category:
Other

Cause:

Action:

ODI-40470
EOF reached but not expected

Category:
Files

Cause:

Action:

ODI-40471
Tried to retrieve an int with an {0} object.

Category:
Other

Cause:

Action:

ODI-40472
Tried to retrieve a short with an {0} object.

Category:
Other

Cause:

Action:

ODI-40473
This resultset accepts only FETCHFORWARD requests

Category:
Other

Cause:

Action:

ODI-40474
This function is unsupported: the software you are using might not be compatible with this driver.

Category:
Other

Cause:

Action:

ODI-40475
Invalid column name

Category:
Other

Cause:

Action:

ODI-40476
Expected a comma.

Category:
Other

Cause:

Action:

ODI-40477
Cannot have a parameter inside a bare statement: {0}

Category:
Other

Cause:

Action:

ODI-40478
Could not transform data.

Category:
Other

Cause:

Action:

ODI-40479
Unrecognized command.

Category:
Other

Cause:

Action:

ODI-40480
Malformed INSERT statement.

Category:
Other

Cause:

Action:

ODI-40481
Invalid COL ALIAS "{0}" for column "{1}"

Category:
Other

Cause:

Action:

ODI-40482
Two selected columns have the same alias: {0}

Category:
Other

Cause:

Action:

ODI-40483
Could not read value {0}

Category:
Other

Cause:

Action:

ODI-40484
Could not read null value

Category:
Other

Cause:

Action:

ODI-40485
Not a ?

Category:
Other

Cause:

Action:

ODI-40486
Could not read value {0}

Category:
Other

Cause:

Action:

ODI-40487
Unknown file format

Category:
Files

Cause:

Action:

ODI-40488
Invalid COL ALIAS "{0}" for column "{1}"

Category:
Other

Cause:

Action:

ODI-40489
Not Supported

Category:
Files

Cause:

Action:

ODI-40490
Datatype {0} is not implemented for now

Category:
Other

Cause:

Action:

ODI-40491
ResultSet already closed. Cannot call next() on it.

Category:
Other

Cause:

Action:

ODI-40492
Property "{0}" is having invalid value "{1}".

Category:
Other

Cause:

Action:

ODI-40493
Parameter "{0}" has been declared twice. Old value : "{1}" New value : "{2}".

Category:
Other

Cause:

Action:

ODI-40494
Value for Parameter "{0}" not specified.

Category:
Other

Cause:

Action:

ODI-40500
Unknown parameter : {0}

Category:
Other

Cause:

Action:

ODI-40501
Syntax: {0}

Category:
Other

Cause:

Action:

ODI-40502
Can"t begin loading while loading another context

Category:
Other

Cause:

Action:

ODI-40503
Creating a new element {0} from the object {1} in DN {2} which contains attributes {3}

Category:
Other

Cause:

Action:

ODI-40504
Found the key {0} for the element {1} in DN {2}

Category:
Other

Cause:

Action:

ODI-40505
Entry {0} in {1} has a key {2} which is different from the original key found: {3}

Category:
Other

Cause:

Action:

ODI-40506
Adding new attribute {0} for object {1}

Category:
Other

Cause:

Action:

ODI-40507
Model Builder

Category:
Other

Cause:

Action:

ODI-40508
Not finished loading!

Category:
Other

Cause:

Action:

ODI-40509
Can"t begin loading while loading another context

Category:
Other

Cause:

Action:

ODI-40510
Not finished loading!

Category:
Other

Cause:

Action:

ODI-40511
Bad element {0} while in level

Category:
Other

Cause:

Action:

ODI-40512
Because an element {0} is not supposed to appear here. Please check your data model.

Category:
Other

Cause:

Action:

ODI-40513
Entry {0} in {1} has a key {2} which is different from the original key found: {3}

Category:
Other

Cause:

Action:

ODI-40514
Not implemented

Category:
Other

Cause:

Action:

ODI-40515
Not implemented

Category:
Other

Cause:

Action:

ODI-40516
Could not add table {0} because the model told us it''s a duplicate. Please try changing the grouping factor.

Category:
Other

Cause:

Action:

ODI-40517
Could not add table {0} because the model told us it''s a duplicate. Please try changing the grouping factor.

Category:
Other

Cause:

Action:

ODI-40518
The table {0} already exists in the model and could not be added

Category:
Other

Cause:

Action:

ODI-40519
The table {0} is a duplicate root

Category:
Other

Cause:

Action:

ODI-40520
The table {0} doesn''t exist

Category:
Other

Cause:

Action:

ODI-40521
A NamingException occurred saying {0} because of {1} with the remaining name {2}

Category:
Other

Cause:

Action:

ODI-40522
Exception {0} occurred saying: {1}

Category:
Other

Cause:

Action:

ODI-40523
Property {0} is invalid

Category:
Other

Cause:

Action:

ODI-40524
Property {0} from the URL is invalid

Category:
Other

Cause:

Action:

ODI-40525
Internal connection is null. This shouldn''t happen that way.

Category:
Other

Cause:

Action:

ODI-40526
A NamingException occured saying: {0} with this explanation: {1} and this remaining name: {2}

Category:
Other

Cause:

Action:

ODI-40527
Could not read alias bundle because an IOException occurred saying: {0}

Category:
Other

Cause:

Action:

ODI-40528
A {0} occurred saying: {1}

Category:
Other

Cause:

Action:

ODI-40529
Could not write alias bundle because an IOException occurred saying {0}

Category:
Other

Cause:

Action:

ODI-40530
The schema is now in a read only mode because the technology is not HSQL

Category:
Other

Cause:

Action:

ODI-40531
Exception {0} occurred saying: {1}

Category:
Other

Cause:

Action:

ODI-40532
Could not find the element for row of table {0}: {1}

Category:
Other

Cause:

Action:

ODI-40533
Element {0} has no identifier so this row could not be updated.

Category:
Other

Cause:

Action:

ODI-40534
Exception getting original attributes of baseDN={0}

Category:
Other

Cause:

Action:

ODI-40535
Key column {0} has a null value though it''s required

Category:
Other

Cause:

Action:

ODI-40536
Deleting attribute {0} from Object {1}

Category:
Other

Cause:

Action:

ODI-40537
Deleting object {0}

Category:
Other

Cause:

Action:

ODI-40538
Creating attribute value {0} in attribute {1} from Object {2}

Category:
Other

Cause:

Action:

ODI-40539
Adding object {0} to the database from row {1}

Category:
Other

Cause:

Action:

ODI-40540
Modifying attribute value {0} to {1} in attribute {2} from Object {3}

Category:
Other

Cause:

Action:

ODI-40541
Adding attribute value {0} in attribute {1} from Object {2}

Category:
Other

Cause:

Action:

ODI-40542
This update is not permitted because it would move the element to another location in the hierarchy.

Category:
Other

Cause:

Action:

ODI-40543
This update is not permitted because it would move this attribute to another element.

Category:
Other

Cause:

Action:

ODI-40544
The attribute {0} cannot exist in an element of class {1}

Category:
Other

Cause:

Action:

ODI-40545
Modifying attribute value {0} to {1} in attribute {2} from Object {3}

Category:
Other

Cause:

Action:

ODI-40546
A user has not been provided

Category:
Other

Cause:

Action:

ODI-40547
Not Supported

Category:
Other

Cause:

Action:

ODI-40548
Parameter {0} has already been specified. Old value : {1} New value : {2}

Category:
Other

Cause:

Action:

ODI-40549
Invalid value specified for {0}

Category:
Other

Cause:

Action:

ODI-40550
Unable to create IntialLdapContext for {0}. Pagination is not possible. Is LDAP server LDAPv3?

Category:
Other

Cause:

Action:

ODI-40551
LdapContext needed for pagination. Found {0}

Category:
Other

Cause:

Action:

ODI-40552
Invalid page size : {0}

Category:
Other

Cause:

Action:

ODI-40553
Unable to get cipher without instance

Category:
Other

Cause:

Action:

ODI-40554
Unable to encrypt LDAP2 password

Category:
Other

Cause:

Action:

ODI-40555
Unable to encrypt LDAP2 password

Category:
Other

Cause:

Action:

ODI-40556
URL must start with {0}

Category:
Other

Cause:

Action:

ODI-40557
objectClass attribute not found for {0} from parent {1}

Category:
Other

Cause:

Action:

ODI-40558
objectClass attribute not found for element with attributes {0}

Category:
Other

Cause:

Action:

ODI-40559
LDAP server URL is mandatory.

Category:
Other

Cause:

Action:

ODI-40700
Schema {0} cannot be dropped because it is referenced by one or more connections.

Category:
Other

Cause:

Action:

ODI-40701
Exception {0} occurred saying: {1}

Category:
Other

Cause:

Action:

ODI-40702
XSD is required for processing flat files

Category:
Other

Cause:

Action:

ODI-40703
Root element name is required for processing flat file

Category:
Other

Cause:

Action:

ODI-40704
The schema {0} already exists. Use the "REPLACE" option to replace the schema

Category:
Other

Cause:

Action:

ODI-40705
The schema parameter is required in the command SET SCHEMA

Category:
Other

Cause:

Action:

ODI-40706
This schema doesn"t exist: {0}

Category:
Other

Cause:

Action:

ODI-40707
No existing schema with this name: "{0}". Please verify that it is the same schema name than the one you specified in your URL connection.

Category:
Other

Cause:

Action:

ODI-40708
Error synchronizing automatically the schema

Category:
Other

Cause:

Action:

ODI-40709
The xml file is required in a LOAD FILE command

Category:
Other

Cause:

Action:

ODI-40710
The schema name is mandatory for the CREATE SCHEMA command

Category:
Other

Cause:

Action:

ODI-40711
This schema has no DTD and cannot be saved to a XML file

Category:
Other

Cause:

Action:

ODI-40712
This table doesn''t exist in the schema so it can''t be the root table: {0}

Category:
Other

Cause:

Action:

ODI-40713
The file parameter is required to write a file

Category:
Other

Cause:

Action:

ODI-40714
Could not find a file to verify: make sure you are on a schema associated with a file or use the "VALIDATE FILE <FileName>" syntax.

Category:
Other

Cause:

Action:

ODI-40715
Exception {0} occurred saying: {1}

Category:
Other

Cause:

Action:

ODI-40716
Parameter {0} has been declared twice. Old value : {1} New value : {2}

Category:
Other

Cause:

Action:

ODI-40717
Unknown parameter : {0}

Category:
Other

Cause:

Action:

ODI-40718
Could not read the input XML data

Category:
Other

Cause:

Action:

ODI-40719
Could not read the XML data because a SAXException occurred saying: {0}

Category:
Other

Cause:

Action:

ODI-40720
Could not read the XML data because the parser is not configured correctly: {0}

Category:
Other

Cause:

Action:

ODI-40721
Could not read the XML data because an IOException occurred saying: {0}

Category:
Other

Cause:

Action:

ODI-40722
The data has been altered: {0} !!!

Category:
Other

Cause:

Action:

ODI-40723
XmlParser not validated.

Category:
Other

Cause:

Action:

ODI-40724
The same connection should have been returned but I got another one

Category:
Other

Cause:

Action:

ODI-40725
Custom varchar column size was not correct: {0} instead of 300

Category:
Other

Cause:

Action:

ODI-40726
Truncate did not truncate a table

Category:
Other

Cause:

Action:

ODI-40727
Custom numeric column size was not correct: {0} instead of 12

Category:
Other

Cause:

Action:

ODI-40728
Could not find the row with a pk=20

Category:
Other

Cause:

Action:

ODI-40729
Error: Dropping of a schema that is referenced by another connection is allowed!

Category:
Other

Cause:

Action:

ODI-40730
Standalone schema type is not compatible with external database storage

Category:
Other

Cause:

Action:

ODI-40733
Creating a data inserter which uses prepared statements

Category:
Other

Cause:

Action:

ODI-40734
An UnsupportedDatatypeException occurred

Category:
Other

Cause:

Action:

ODI-40735
Model type not supported: {0}. Expecting one of dtd, xsd.

Category:
Other

Cause:

Action:

ODI-40736
IOException occurred

Category:
Other

Cause:

Action:

ODI-40737
A parsing exception occurred

Category:
Other

Cause:

Action:

ODI-40738
A SAXException was caught while reading the model saying: {0}

Category:
Other

Cause:

Action:

ODI-40739
A ParserConfigurationException was caught while reading the model

Category:
Other

Cause:

Action:

ODI-40740
A duplicate element was found in the DTD/XSD

Category:
Other

Cause:

Action:

ODI-40741
A duplicate type was found in the DTD/XSD

Category:
Other

Cause:

Action:

ODI-40742
An unknown element was found in the DTD/XSD

Category:
Other

Cause:

Action:

ODI-40743
Namespace not found

Category:
Other

Cause:

Action:

ODI-40744
Ambiguous name

Category:
Other

Cause:

Action:

ODI-40745
Malformed QName

Category:
Other

Cause:

Action:

ODI-40746
Unsupported model

Category:
Other

Cause:

Action:

ODI-40747
Duplicate attribute

Category:
Other

Cause:

Action:

ODI-40748
Duplicate reference to an element

Category:
Other

Cause:

Action:

ODI-40749
Conflicting namespaces

Category:
Other

Cause:

Action:

ODI-40750
The model generated by the model mapper was not accepted by a validator

Category:
Other

Cause:

Action:

ODI-40751
An XMLUnsupportedException was caught

Category:
Other

Cause:

Action:

ODI-40752
The DTD file "{0}" doesn"t exist: {0}

Category:
Other

Cause:

Action:

ODI-40753
No DTD is associated to the file {0}

Category:
Other

Cause:

Action:

ODI-40754
File {0} is already locked by another instance of the XML driver.

Category:
Other

Cause:

Action:

ODI-40755
Could not lock file {0}: {1}

Category:
Other

Cause:

Action:

ODI-40756
No DTD was found so no data was retrieved

Category:
Other

Cause:

Action:

ODI-40757
An exception occurred while reading the file

Category:
Other

Cause:

Action:

ODI-40758
Malformed qualified name in root properties: {0}

Category:
Other

Cause:

Action:

ODI-40759
Both the schema "{0}" and the file "{1}" have been modified!

Category:
Other

Cause:

Action:

ODI-40760
The root table ({0}) doesn''t exist!

Category:
Other

Cause:

Action:

ODI-40761
Not enough memory to read the XML file

Category:
Other

Cause:

Action:

ODI-40762
Cannot write the file because this schema is opened in a read-only mode.

Category:
Other

Cause:

Action:

ODI-40763
Invalid property definition: "{0}" in "{1}"

Category:
Other

Cause:

Action:

ODI-40764
File {0} is not locked or cannot be unlocked.

Category:
Other

Cause:

Action:

ODI-40765
Cannot write to an URL.

Category:
Other

Cause:

Action:

ODI-40766
Could not delete existing file {0}.

Category:
Other

Cause:

Action:

ODI-40767
Could not rename existing file {0} to make a backup

Category:
Other

Cause:

Action:

ODI-40768
Could not save the file {0} because a {1} occurred and said: {2}

Category:
Other

Cause:

Action:

ODI-40769
Could not close the file. You should probably close your application: {0}

Category:
Other

Cause:

Action:

ODI-40770
Could not delete the output file after an error occurred

Category:
Other

Cause:

Action:

ODI-40771
Could not restore the original file after an error occurred

Category:
Other

Cause:

Action:

ODI-40772
No DTD was found so no data was retrieved

Category:
Other

Cause:

Action:

ODI-40773
Connection type not supported: {0}

Category:
Other

Cause:

Action:

ODI-40774
No DTD was found so no data was retrieved

Category:
Other

Cause:

Action:

ODI-40775
Should not occur for prefix generation

Category:
Other

Cause:

Action:

ODI-40776
Could not free the file {0}. Verify that no .lck file is left.

Category:
Other

Cause:

Action:

ODI-40777
Found PCDATA in element {0} with values ({1})

Category:
Other

Cause:

Action:

ODI-40778
Attribute {0} of element {1} doesn"t exist in the DTD.

Category:
Other

Cause:

Action:

ODI-40779
Root element was not found in the XML Model

Category:
Other

Cause:

Action:

ODI-40780
Root element is ambiguous in the XML Model

Category:
Other

Cause:

Action:

ODI-40781
Could not find the prefix {0}

Category:
Other

Cause:

Action:

ODI-40782
Could not find the namespace for the root element

Category:
Other

Cause:

Action:

ODI-40783
Root element has a malformed name

Category:
Other

Cause:

Action:

ODI-40784
Prefix {0} should exist

Category:
Other

Cause:

Action:

ODI-40785
Malformed QName: {0}

Category:
Other

Cause:

Action:

ODI-40786
Prefix not found: {0}

Category:
Other

Cause:

Action:

ODI-40787
Ambiguous qname for an attribute: {0}

Category:
Other

Cause:

Action:

ODI-40788
Element {0} is ambiguous and was found in more than one namespace: {1}, {2}

Category:
Other

Cause:

Action:

ODI-40789
Element {0} doesn"t match the DTD

Category:
Other

Cause:

Action:

ODI-40790
Could not find parent element {0}

Category:
Other

Cause:

Action:

ODI-40791
Element {0} doesn''t match the DTD

Category:
Other

Cause:

Action:

ODI-40792
Prefix not found: {0}

Category:
Other

Cause:

Action:

ODI-40793
Malformed QName: {0}

Category:
Other

Cause:

Action:

ODI-40794
Element {0} is ambiguous and was found in more than one namespace

Category:
Other

Cause:

Action:

ODI-40795
Element {0} is ambiguous and was found in more than one namespace

Category:
Other

Cause:

Action:

ODI-40796
Conflicting namespaces: {0} => {1}

Category:
Other

Cause:

Action:

ODI-40797
Namespace {0} was not declared in the model

Category:
Other

Cause:

Action:

ODI-40798
Unknown type: {0}

Category:
Other

Cause:

Action:

ODI-40799
Root element "{0}" of XML file doesn"t match the DTD/XSD element with name "{1}" from namespace "{2}" set as root element

Category:
Other

Cause:

Action:

ODI-40800
No root found!

Category:
Other

Cause:

Action:

ODI-40801
Ambiguous name: {0}

Category:
Other

Cause:

Action:

ODI-40802
Namespace not found for {0}

Category:
Other

Cause:

Action:

ODI-40803
Malformed qualified name {0}

Category:
Other

Cause:

Action:

ODI-40804
Empty table for multiple links in attribute {0}

Category:
Other

Cause:

Action:

ODI-40805
Unknown link type: {0}

Category:
Other

Cause:

Action:

ODI-40806
Multiple roots found: {0} and {1}. Use the parameter 'root_elt' in the URL to choose the root element.

Category:
Other

Cause:

Action:

ODI-40807
No root found in the DTD file

Category:
Other

Cause:

Action:

ODI-40808
Should not occur {0}

Category:
Other

Cause:

Action:

ODI-40809
Creating a RDB model from an XML model is currently not supported

Category:
Other

Cause:

Action:

ODI-40810
Creating an XML model from a RDB model is currently not supported

Category:
Other

Cause:

Action:

ODI-40811
No root on model

Category:
Other

Cause:

Action:

ODI-40812
The table {0} which is linked to attribute {1} was not found

Category:
Other

Cause:

Action:

ODI-40813
Unknown attribute: {0}

Category:
Other

Cause:

Action:

ODI-40814
Unknown link type: {0}

Category:
Other

Cause:

Action:

ODI-40815
Ambiguous name: {0}

Category:
Other

Cause:

Action:

ODI-40816
Bad attribute: {0} in element

Category:
Other

Cause:

Action:

ODI-40817
Namespace not found: {0}

Category:
Other

Cause:

Action:

ODI-40818
Internal error: expected to find PCData in element {0}

Category:
Other

Cause:

Action:

ODI-40819
Malformed QName: {0}

Category:
Other

Cause:

Action:

ODI-40820
*** FATAL *** A duplicate root has been found: {0}

Category:
Other

Cause:

Action:

ODI-40821
*** FATAL *** The potential root is not in the model: {0}

Category:
Other

Cause:

Action:

ODI-40822
Duplicate attribute: {0}

Category:
Other

Cause:

Action:

ODI-40823
Type unsupported for PCDATA attribute of element

Category:
Other

Cause:

Action:

ODI-40824
Two namespaces are in conflict and we cannot build aliases: {0}

Category:
Other

Cause:

Action:

ODI-40825
*** FATAL *** Could not create a table because it already exists in the model.

Category:
Other

Cause:

Action:

ODI-40826
A Qualified name cannot begin with a colon

Category:
Other

Cause:

Action:

ODI-40827
A Qualified name cannot end with a colon

Category:
Other

Cause:

Action:

ODI-40828
SnpsXmlNamespaceNotFoundException occured: Should not occur while setting prefixes

Category:
Other

Cause:

Action:

ODI-40829
This is a fixed namespace and elements cannot be added to it

Category:
Other

Cause:

Action:

ODI-40830
The request type is different

Category:
Other

Cause:

Action:

ODI-40831
The request command is different

Category:
Other

Cause:

Action:

ODI-40832
A parameter is missing

Category:
Other

Cause:

Action:

ODI-40833
A parameter has a bad value

Category:
Other

Cause:

Action:

ODI-40834
This token was not expected anymore: {0}

Category:
Other

Cause:

Action:

ODI-40835
Function not implemented yet: {0}

Category:
Other

Cause:

Action:

ODI-40836
Cannot drop the default schema

Category:
Other

Cause:

Action:

ODI-40837
An error occurred during the creation of the schema: {0}

Category:
Other

Cause:

Action:

ODI-40838
An error occurred in the cleanup of the schema: {0}

Category:
Other

Cause:

Action:

ODI-40839
InvalidTableException said: {0}

Category:
Other

Cause:

Action:

ODI-40840
The table {0} already exists in the schema {1}.

Category:
Other

Cause:

Action:

ODI-40841
Could not create schema with URL "{0}"

Category:
Other

Cause:

Action:

ODI-40842
As no XML and no DTD were provided, the XML schema cannot be created

Category:
Other

Cause:

Action:

ODI-40843
No DTD found and no XML file provided: the XML schema cannot be created

Category:
Other

Cause:

Action:

ODI-40844
Could not generate the DTD because the file could not be created. Verify that you have write permission in the directory.

Category:
Other

Cause:

Action:

ODI-40845
While generating the DTD from the XML file, a "{0}" exception occurred saying: {1}

Category:
Other

Cause:

Action:

ODI-40846
Could not close the file because an IOException occurred saying: {0}

Category:
Other

Cause:

Action:

ODI-40847
An UnupportedDatatypeException occurred saying: {0}

Category:
Other

Cause:

Action:

ODI-40848
Could not find the file called {0}

Category:
Other

Cause:

Action:

ODI-40849
IOException reading file called {0}

Category:
Other

Cause:

Action:

ODI-40850
Unsupported DB property "{0}"

Category:
Other

Cause:

Action:

ODI-40851
Table {0} not found in schema {1}

Category:
Other

Cause:

Action:

ODI-40852
The default schema cannot be read/write

Category:
Other

Cause:

Action:

ODI-40853
The schema {0} cannot be set read/write because it has no associated file

Category:
Other

Cause:

Action:

ODI-40854
No file provided for synchronization. Use CREATE FILE <file> FROM <schema> command

Category:
Other

Cause:

Action:

ODI-40855
Table {0} already exists but it doesn"t have the correct number of columns

Category:
Other

Cause:

Action:

ODI-40856
Column {0} doesn''t exist in table {1}, it is required for this DTD

Category:
Other

Cause:

Action:

ODI-40857
Expected one of auto, xml or xsd for parameter ns_prefix_generation

Category:
Other

Cause:

Action:

ODI-40858
Found that the file references the DTD or XSD: {0}

Category:
Other

Cause:

Action:

ODI-40859
Could not read the file to get its associated schema because an IOException occurred saying {0}

Category:
Other

Cause:

Action:

ODI-40860
Could not read the file to get its associated schema because a SAXException occurred saying {0}

Category:
Other

Cause:

Action:

ODI-40861
Could not read the file to get its associated schema because a ParserConfigurationException occurred saying {0}

Category:
Other

Cause:

Action:

ODI-40862
No DTD was provided and the property "generate_dtd" is set to no

Category:
Other

Cause:

Action:

ODI-40863
The parameter generate_dtd has a bad value: {0} . One of 'AUTO', 'YES', 'NO' was expected

Category:
Other

Cause:

Action:

ODI-40864
XSD {0} was found

Category:
Other

Cause:

Action:

ODI-40865
No DTD named {0} was found so the XML schema could not be created

Category:
Other

Cause:

Action:

ODI-40866
This schema is in a {0} state and cannot be opened in another state.

Category:
Other

Cause:

Action:

ODI-40867
Could not connect on schema because it is {0}

Category:
Other

Cause:

Action:

ODI-40868
The path {0} doesn''t exist

Category:
Other

Cause:

Action:

ODI-40869
The path {0} is not a directory

Category:
Other

Cause:

Action:

ODI-40870
You already have a schema opened on this file with another name: {0}

Category:
Other

Cause:

Action:

ODI-40871
Duplicate attribute where no attribute should have been set yet.

Category:
Other

Cause:

Action:

ODI-40872
Unsupported exception saying {0}

Category:
Other

Cause:

Action:

ODI-40873
There are several root tables and the unload is not supported in this case

Category:
Other

Cause:

Action:

ODI-40874
Expected to find attribute {0}

Category:
Other

Cause:

Action:

ODI-40875
Something unexpected occured. Expected to find datatype {0}

Category:
Other

Cause:

Action:

ODI-40876
Extension found in an object of type {0} is not permitted.

Category:
Other

Cause:

Action:

ODI-40877
Cannot merge types for element {0}.

Category:
Other

Cause:

Action:

ODI-40878
Restriction violated : {0}

Category:
Other

Cause:

Action:

ODI-40879
An IOException occured while including another schema saying {0}

Category:
Other

Cause:

Action:

ODI-40880
A ParserConfigurationException occured while including another schema saying {0}

Category:
Other

Cause:

Action:

ODI-40881
Unexpected element of type {0}

Category:
Other

Cause:

Action:

ODI-40882
Cannot add a restriction!: {0}

Category:
Other

Cause:

Action:

ODI-40883
Cannot add a restriction on a non simple type or attribute

Category:
Other

Cause:

Action:

ODI-40884
Extension found outside an element

Category:
Other

Cause:

Action:

ODI-40885
Type {0} was not found

Category:
Other

Cause:

Action:

ODI-40886
Cannot merge types for element "{0}"

Category:
Other

Cause:

Action:

ODI-40887
Unexpected element of type {0} in hierarchy before simple type

Category:
Other

Cause:

Action:

ODI-40888
Unexpected element of type {0}

Category:
Other

Cause:

Action:

ODI-40889
Could not affect complex type to object of type {0}

Category:
Other

Cause:

Action:

ODI-40890
Unexpected element of type {0}

Category:
Other

Cause:

Action:

ODI-40891
An element has no name and doesn''t refer to another element

Category:
Other

Cause:

Action:

ODI-40892
Cannot add an element to an attributeGroup (wanting to add {0} to group {1})

Category:
Other

Cause:

Action:

ODI-40893
Cannot add an element to an object of type {0}

Category:
Other

Cause:

Action:

ODI-40894
Could not find namespace: {0}

Category:
Other

Cause:

Action:

ODI-40895
Conflicting Namespace Error: Should not occur: {0}

Category:
Other

Cause:

Action:

ODI-40896
Unknown prefix: {0}

Category:
Other

Cause:

Action:

ODI-40897
Cannot handle type [{0}] as a simple type

Category:
Other

Cause:

Action:

ODI-40898
Element {0} referenced in group {1} was not found

Category:
Other

Cause:

Action:

ODI-40899
Attributes' group {0} not found in the file.

Category:
Other

Cause:

Action:

ODI-40900
Duplicate attribute: {0}

Category:
Other

Cause:

Action:

ODI-40901
Unsupported exception: {0}

Category:
Other

Cause:

Action:

ODI-40902
Element group {0} not found in the file.

Category:
Other

Cause:

Action:

ODI-40903
Duplicate reference while adding an element of a group: {0}

Category:
Other

Cause:

Action:

ODI-40904
Unsupported exception while adding an element of a group: {0}

Category:
Other

Cause:

Action:

ODI-40905
Namespace {0} for element {1} referenced in group {2} was not found.

Category:
Other

Cause:

Action:

ODI-40906
Element {0} referenced in group {1} has an ambiguous name

Category:
Other

Cause:

Action:

ODI-40907
An object of one of these types was expected in the hierarchy: element, type, attribute, attribute group

Category:
Other

Cause:

Action:

ODI-40908
No more pending objects left in hierarchy

Category:
Other

Cause:

Action:

ODI-40909
An object of one of these types was expected in the hierarchy: element, type, attribute, attribute group

Category:
Other

Cause:

Action:

ODI-40910
Cannot add element {0} to type {1} because it doesn"t handle references.

Category:
Other

Cause:

Action:

ODI-40911
One pending element was not found: {0}

Category:
Other

Cause:

Action:

ODI-40912
Simple type {0} has a restriction on a type {1}

Category:
Other

Cause:

Action:

ODI-40913
The object of type {0} is missing type {1} but don't know how to deal with it.

Category:
Other

Cause:

Action:

ODI-40914
Element {0} is missing but is referenced

Category:
Other

Cause:

Action:

ODI-40915
Type {0} is missing but is needed.

Category:
Other

Cause:

Action:

ODI-40916
Element {0} has no type.

Category:
Other

Cause:

Action:

ODI-40917
One pending element's namespace was not found: {0}

Category:
Other

Cause:

Action:

ODI-40918
One pending element has an ambiguous name: {0}

Category:
Other

Cause:

Action:

ODI-40919
Cannot add element {0} to type {1} because it doesn''t handle references.

Category:
Other

Cause:

Action:

ODI-40920
An attribute must have a simple type

Category:
Other

Cause:

Action:

ODI-40921
Could not find the root element that we've just set.

Category:
Other

Cause:

Action:

ODI-40922
This qualified name is malformed: {0}

Category:
Other

Cause:

Action:

ODI-40923
Inner type of element {0} is not defined or is not a complex type

Category:
Other

Cause:

Action:

ODI-40924
Renamed column {0} to {1}

Category:
Other

Cause:

Action:

ODI-40925
Should not occur

Category:
Other

Cause:

Action:

ODI-40926
Internal error

Category:
Other

Cause:

Action:

ODI-40927
Not Supported

Category:
Other

Cause:

Action:

ODI-40928
Not supported for XML driver commands

Category:
Other

Cause:

Action:

ODI-40929
Property {0} has invalid value {1}

Category:
Other

Cause:

Action:

ODI-40930
Root element {0} specified by user not a global element in the NXSD

Category:
Other

Cause:

Action:

ODI-40931
Unrecognised request type for {0}

Category:
Other

Cause:

Action:

ODI-40932
Unable to find root element in DTD.

Category:
Other

Cause:

Action:

ODI-40933
Unable to build XSD from DTD.

Category:
Other

Cause:

Action:

ODI-40934
The schema {0} is not created using the appropriate compatibility mode.

Category:
Other

Cause:

Action:

ODI-40935
The schema {0} was created with correct compatibility mode, but has incorrect XML model type

Category:
Other

Cause:

Action:

ODI-40936
Namespace URI for the prefix {0} was not found in the XSD/DTD or XML

Category:
Other

Cause:

Action:

ODI-40937
Encountered one more close tag while no more open tags were found

Category:
Other

Cause:

Action:

ODI-40938
Error splitting prefixed string {0}

Category:
Other

Cause:

Action:

ODI-40939
The XML construct "{0}" in element "{1}" from type "{2}" is not supported by XML JDBC driver

Category:
Other

Cause:

Action:

ODI-40940
No global elements were found in the XSD

Category:
Other

Cause:

Action:

ODI-40941
Requested root element {0} was not found in the XSD

Category:
Other

Cause:

Action:

ODI-40942
Ending on "{0}" but needed to find "{1}"

Category:
Other

Cause:

Action:

ODI-40945
XSD parser ecnountered error parsing XSD/DTD. Check validity.

Category:
Other

Cause:

Action:

ODI-40946
Error processing XSD/DTD

Category:
Other

Cause:

Action:

ODI-40947
Unable to write xpath mapping information

Category:
Other

Cause:

Action:

ODI-40948
Could not find namespace URI {0} in XML model for {1}

Category:
Other

Cause:

Action:

ODI-40949
Old object type found for namespace {0}

Category:
Other

Cause:

Action:

ODI-40951
Unable to find namespace URI : {0}

Category:
Other

Cause:

Action:

ODI-40952
Element {0} of type {1} at xpath {2} appears to be same as element {3} of type {4} at xpath {5}.

Category:
Other

Cause:

Action:

ODI-40953
Prefix "{0}" is already mapped to "{1}" in current XML scope. New uri : "{2}"

Category:
Other

Cause:

Action:

ODI-40956
Root element {0} is substitutionGroup head. This is not allowed.

Category:
Other

Cause:

Action:

ODI-40957
Unable to resolve path of XSD "{0}"

Category:
Other

Cause:

Action:

ODI-40958
Illegal state. Currently coalescing for "{0}".

Category:
Other

Cause:

Action:

ODI-40959
Illegal state. Not coalescing yet.

Category:
Other

Cause:

Action:

ODI-40960
Unknown object "{0}" found

Category:
Other

Cause:

Action:

ODI-40961
You cannot use v1 compatibility flag along with v3 mode

Category:
Other

Cause:

Action:

ODI-40962
Error occurred checking if table "{0}" exists

Category:
Other

Cause:

Action:

ODI-40963
XSD does not define "anyAttribute" for {0}, but found it in DB.

Category:
Other

Cause:

Action:

ODI-40964
Element "{0}" is defined in XSD to have "any" element child, but could not find it in model.

Category:
Other

Cause:

Action:

ODI-40965
Illegal metadata on element "{0}". Element results in column, but has table metadata.

Category:
Other

Cause:

Action:

ODI-40966
Column metadata set on element with xpath "{0}" while it has child : "{1}"

Category:
Other

Cause:

Action:

ODI-40967
Illegal metadata on attribute "{0}" with xpath "{1}". Attribute may only have column metadata.

Category:
Other

Cause:

Action:

ODI-40968
Property only supported for complex file driver when inxb/is_nxsd_based=true.

Category:
Other

Cause:

Action:

ODI-40969
Trying to use "{0}" data type with Statement not supported. {1} xPath "{2}". Either user has requested not to use PreparedStatement or your DB/driver does not support PreparedStatement

Category:
Other

Cause:

Action:

ODI-40970
Trying to use table "{0}" used by "{1}" for "{2}"

Category:
Other

Cause:

Action:

ODI-40971
When user specifies DB type, length and scale must also be specified. Not done for "{0}"

Category:
Other

Cause:

Action:

ODI-40972
More than one "any" associated with element "{0}"

Category:
Other

Cause:

Action:

ODI-40973
URL must start with {0}

Category:
Other

Cause:

Action:

ODI-40974
Element with xpath {0} already set with recursion head as {1}

Category:
Other

Cause:

Action:

ODI-40975
Element with xpath {0} already set with recursion on {1}

Category:
Other

Cause:

Action:

ODI-40976
xpath {0} already seen with {1}

Category:
Other

Cause:

Action:

ODI-40977
URL syntax error {0}. Consult driver documentation

Category:
Other

Cause:

Action:

ODI-41000
Groovy code in stage {0} could not be compiled

Category:
Other

Cause:

Action:

ODI-41001
Groovy code in stage {0} could not be converted to GroovySource

Category:
Other

Cause:

Action:

ODI-41002
GroovySource for stage {0} is null

Category:
Other

Cause:

Action:

ODI-41003
Groovy code for stage {0} pointed by {1} could not be located as file or classpath resource

Category:
Other

Cause:

Action:

ODI-41004
Groovy script for stage {0} could not be read

Category:
Other

Cause:

Action:

ODI-41005
Groovy script for stage {0} could not be compiled

Category:
Other

Cause:

Action:

ODI-41006
Java class {0} for stage {1} could not be found

Category:
Other

Cause:

Action:

ODI-41007
Stage definition {0} is invalid. Need at least one of "code", "groovyScript" or "javaClass"

Category:
Other

Cause:

Action:

ODI-41008
Unable to find constructor with right signature for stage {0}. Expected constructor with params {1}

Category:
Other

Cause:

Action:

ODI-41009
Error instantiating stage {0}

Category:
Other

Cause:

Action:

ODI-41010
Stage {0} incorrectly attempts to create an InputDecorator. This class is not meant for instantiation.

Category:
Other

Cause:

Action:

ODI-41011
Stage {0} incorrectly attempts to create an OutputDecorator. This class is not meant for instantiation.

Category:
Other

Cause:

Action:

ODI-41012
LinkageError trying to instantiate Java class {0} for stage {1}

Category:
Other

Cause:

Action:

ODI-41013
InitializationError trying to instantiate Java class {0} for stage {1}

Category:
Other

Cause:

Action:

ODI-50000
Java exception thrown: {0}.

Category:
Programmatic

Cause:
A java exception was thrown during processing.

Action:
Internal Error: contact Oracle support.

ODI-999999
Expression reference not found: {0}.

Category:
Programmatic

Cause:
The expression being parsed has a column reference that cannot be found.

Action:
Check the expression

22
OGGV-00001 to OGGV-600013

OGGV-00001
Compare Pair Mappings are valid

Category:
Other

Cause:

Action:

OGGV-00002
Compare Pair Key Mapping are invalid

Category:
Other

Cause:

Action:

OGGV-00003
Compare Pair Comparison Column Mappings are invalid

Category:
Other

Cause:

Action:

OGGV-00004
Compare Pair Mappings are invalid

Category:
Other

Cause:

Action:

OGGV-00005
Compare Pair Mappings are no longer valid (possible changes in the datasources)

Category:
Other

Cause:

Action:

OGGV-00006
The operation was completed successfully.

Category:
Other

Cause:

Action:

OGGV-00007
The operation failed due to validation error(s).

Category:
Other

Cause:

Action:

OGGV-00008
This job is already added.

Category:
Other

Cause:

Action:

OGGV-00009
A Favorite Job/Shortcut with this name already exists. Please choose another name.

Category:
Other

Cause:

Action:

OGGV-00010
Application Error

Category:
Other

Cause:

Action:

OGGV-00011
An unexpected error occurred. Please contact the system administrator. Original error message was: {0}

Category:
Other

Cause:

Action:

OGGV-00012
An error occurred when trying to update the connection. The operation was not completed.

Category:
Other

Cause:

Action:

OGGV-00013
The operation was not completed. Please select a connection to proceed.

Category:
Other

Cause:

Action:

OGGV-00014
An error occurred when trying to update the group. The operation was not completed.

Category:
Other

Cause:

Action:

OGGV-00015
The operation was not completed. Please select a group to proceed.

Category:
Other

Cause:

Action:

OGGV-00016
The operation was not completed. Please select a profile to proceed.

Category:
Other

Cause:

Action:

OGGV-00017
The operation was not completed. Please select a shortcut to proceed.

Category:
Other

Cause:

Action:

OGGV-00018
Please specify or verify the datasource type

Category:
Other

Cause:

Action:

OGGV-00019
Please enter a valid host name.

Category:
Other

Cause:

Action:

OGGV-00020
White spaces are not allowed.

Category:
Other

Cause:

Action:

OGGV-00021
Invalid character found: {1}

Category:
Other

Cause:

Action:

OGGV-00022
White spaces are not allowed.

Category:
Other

Cause:

Action:

OGGV-00023
Invalid character found: {1}

Category:
Other

Cause:

Action:

OGGV-00024
Value is required.

Category:
Other

Cause:

Action:

OGGV-00025
Conversion error

Category:
Other

Cause:

Action:

OGGV-00026
Specified attribute is not between the expected values of {0} and {1}.

Category:
Other

Cause:

Action:

OGGV-00027
Maximum length is {0}.

Category:
Other

Cause:

Action:

OGGV-00028
Specified value is not a valid number.

Category:
Other

Cause:

Action:

OGGV-00029
Specified value is not a valid number.

Category:
Other

Cause:

Action:

OGGV-00030
Type specified does not match correct type. Correct type is {1}.

Category:
Other

Cause:

Action:

OGGV-00031
The connection {0} could not be found. Please verify that the name is correct.

Category:
Other

Cause:

Action:

OGGV-00032
A job named {0} already exists. Job name is case insensitive and must be unique.

Category:
Other

Cause:

Action:

OGGV-00033
The profile {0} could not be found. Please verify that the name is correct.

Category:
Other

Cause:

Action:

OGGV-00034
The group {0} could not be found. Please verify that the name is correct.

Category:
Other

Cause:

Action:

OGGV-00035
An error occurred when trying to load metadata information (Indexes) for [{0}]. Connection used was [{1}].

Category:
Other

Cause:

Action:

OGGV-00036
An error occurred when trying to load metadata information (Columns) for [{0}]. Connection used was [{1}].

Category:
Other

Cause:

Action:

OGGV-00037
A connection named {0} already exists. Connection name is case insensitive and must be unique.

Category:
Other

Cause:

Action:

OGGV-00038
A group named {0} already exists. Group name is case insensitive and must be unique.

Category:
Other

Cause:

Action:

OGGV-00039
Finished details will only be available when the entire job finishes.

Category:
Other

Cause:

Action:

OGGV-00040
This compare pair did not complete successfully, therefore the charts will only display the results obtained before the failure.

Category:
Other

Cause:

Action:

OGGV-00041
You need to select a Connection to continue.

Category:
Other

Cause:

Action:

OGGV-00042
You need to select a Group to continue.

Category:
Other

Cause:

Action:

OGGV-00043
You need to select a Job to continue.

Category:
Other

Cause:

Action:

OGGV-00044
You need to select a Profile to continue.

Category:
Other

Cause:

Action:

OGGV-00045
The job {0} could not be found. Please verify that the name is correct.

Category:
Other

Cause:

Action:

OGGV-00046
You cannot change the DBMS type of the manager.

Category:
Other

Cause:

Action:

OGGV-00047
The Compare Pair referenced no longer exists.

Category:
Other

Cause:

Action:

OGGV-00048
You cannot set Compare Pairs status filter to "{0}" when run options is "Review Previous Out-Of-Sync Results".

Category:
Other

Cause:

Action:

OGGV-00049
General datasource error: {0}

Category:
Other

Cause:

Action:

OGGV-00050
The requested object was not found in the database.

Category:
Other

Cause:

Action:

OGGV-00051
It was not possible to delete the object: {0}

Category:
Other

Cause:

Action:

OGGV-00052
Could not find the password file: [{0}]

Category:
Other

Cause:

Action:

OGGV-00053
Could not read the password from file: [{0}]

Category:
Other

Cause:

Action:

OGGV-00054
Unable to locate the server.

Category:
Other

Cause:

Action:

OGGV-00055
There was a communication issue with Veridata Server.

Category:
Other

Cause:

Action:

OGGV-00056
GoldenGate Veridata Server could not be reached. Please verify if it is currently running and that your configuration is correct.

Category:
Other

Cause:

Action:

OGGV-00057
Your session is invalid. Please log on again.

Category:
Other

Cause:

Action:

OGGV-00058
Connection to Veridata Server timed out. Please try again.

Category:
Other

Cause:

Action:

OGGV-00059
Could not load comparison report {0}: {1}

Category:
Other

Cause:

Action:

OGGV-00060
Command file name was not provided

Category:
Other

Cause:

Action:

OGGV-00061
Path to chunks was not provided

Category:
Other

Cause:

Action:

OGGV-00062
Cannot parse control file: [{0}]

Category:
Other

Cause:

Action:

OGGV-00063
Cannot create metadata

Category:
Other

Cause:

Action:

OGGV-00064
Cannot create operation summary

Category:
Other

Cause:

Action:

OGGV-00065
Cannot create differences by column

Category:
Other

Cause:

Action:

OGGV-00066
Cannot get chunks info

Category:
Other

Cause:

Action:

OGGV-00067
Cannot get operation details because: [{0}]

Category:
Other

Cause:

Action:

OGGV-00068
Cannot initialize Velocity Engine: [{0}]

Category:
Other

Cause:

Action:

OGGV-00069
Cannot apply Velocity Template: [{0}]

Category:
Other

Cause:

Action:

OGGV-00070
The Source Schema is required.

Category:
Other

Cause:

Action:

OGGV-00071
The Target Schema is required.

Category:
Other

Cause:

Action:

OGGV-00072
The Source Schema is required.

Category:
Other

Cause:

Action:

OGGV-00073
The Target Schema is required.

Category:
Other

Cause:

Action:

OGGV-00074
The Source Schema is required.

Category:
Other

Cause:

Action:

OGGV-00075
The Target Schema is required.

Category:
Other

Cause:

Action:

OGGV-00076
The Source Schema is required.

Category:
Other

Cause:

Action:

OGGV-00077
The Target Schema is required.

Category:
Other

Cause:

Action:

OGGV-00078
The Source Schema is required.

Category:
Other

Cause:

Action:

OGGV-00079
The Target Schema is required.

Category:
Other

Cause:

Action:

OGGV-00080
The Source Schema is required.

Category:
Other

Cause:

Action:

OGGV-00081
The Target Schema is required.

Category:
Other

Cause:

Action:

OGGV-00082
The Source Catalog is required.

Category:
Other

Cause:

Action:

OGGV-00083
The Target Catalog is required.

Category:
Other

Cause:

Action:

OGGV-00084
The Source File Pattern is required.

Category:
Other

Cause:

Action:

OGGV-00085
The Target File Pattern is required.

Category:
Other

Cause:

Action:

OGGV-00086
The Source Table is required.

Category:
Other

Cause:

Action:

OGGV-00087
The Target Table is required.

Category:
Other

Cause:

Action:

OGGV-00088
The Source Table is required.

Category:
Other

Cause:

Action:

OGGV-00089
The Target Table is required.

Category:
Other

Cause:

Action:

OGGV-00090
The Source Table is required.

Category:
Other

Cause:

Action:

OGGV-00091
The Target Table is required.

Category:
Other

Cause:

Action:

OGGV-00092
The Source File/Table is required.

Category:
Other

Cause:

Action:

OGGV-00093
The Target File/Table is required.

Category:
Other

Cause:

Action:

OGGV-00094
Connection "{0}" still referenced, you cannot delete it.

Category:
Other

Cause:

Action:

OGGV-00095
Connection "{0}" does not exist

Category:
Other

Cause:

Action:

OGGV-00096
Connection "{0}" already exists

Category:
Other

Cause:

Action:

OGGV-00097
{0} handle is not valid.

Category:
Other

Cause:

Action:

OGGV-00100
Bad password

Category:
Other

Cause:

Action:

OGGV-00102
Bad authorization handle

Category:
Other

Cause:

Action:

OGGV-00103
Cannot connect to "{0}"

Category:
Other

Cause:

Action:

OGGV-00104
Cannot start meta lookup

Category:
Other

Cause:

Action:

OGGV-00105
Group must be created empty

Category:
Other

Cause:

Action:

OGGV-00106
Compare pair id must be 0 to create

Category:
Other

Cause:

Action:

OGGV-00107
Element <{0}> cannot be Null

Category:
Other

Cause:

Action:

OGGV-00108
Cannot start RHS agent, mgr={0}, port={1}, error={2}

Category:
Other

Cause:

Action:

OGGV-00109
Catalog lookup failed, mgr={0}, port={1}

Category:
Other

Cause:

Action:

OGGV-00110
Schema lookup failed, mgr={0}, port={1}, catalog={2}

Category:
Other

Cause:

Action:

OGGV-00111
Tables lookup failed, mgr={0}, port={1}, catalog={2}, schema={3}

Category:
Other

Cause:

Action:

OGGV-00112
Column lookup failed, mgr={0}, port={1}, catalog={2}, schema={3}, table={4}

Category:
Other

Cause:

Action:

OGGV-00113
Index lookup failed, mgr={0}, port={1}, catalog={2}, schema={3}, table={4}

Category:
Other

Cause:

Action:

OGGV-00114
Communication error ({0}, {1})

Category:
Other

Cause:

Action:

OGGV-00118
Agent message ({0}): {1}

Category:
Other

Cause:

Action:

OGGV-00119
Agent remote message ({0}): {1}

Category:
Other

Cause:

Action:

OGGV-00120
Could not log into database, check username and password

Category:
Other

Cause:

Action:

OGGV-00121
Test fault with parameters. int64: 0x{0}, uint64: {1}, int32: {2}, uint32: {3}, int16: {4}, uint16: {5}, int8 {6}, uint8 {7}, char * {8}, char * {9}, char * {10}, char * {11}, char * {12}, void * 0x{13}, double {14}, long double {15}, ptrdiff_t {16}, size_t {17}.

Category:
Other

Cause:

Action:

OGGV-00123
Internal error.

Category:
Other

Cause:

Action:

OGGV-00124
{0} "{1}" has changed since it was selected, please try again.

Category:
Other

Cause:

Action:

OGGV-00126
Bad meta-session handle

Category:
Other

Cause:

Action:

OGGV-00127
Column validation failed.

Category:
Other

Cause:

Action:

OGGV-00128
Index validation failed.

Category:
Other

Cause:

Action:

OGGV-00129
{0} index "{1}" does not exist.

Category:
Other

Cause:

Action:

OGGV-00130
{0} table schema has changed. Please check that the table still exists and column positions and datatypes have not changed.

Category:
Other

Cause:

Action:

OGGV-00131
Column mapping is invalid, please check the datatypes and comparison formats.

Category:
Other

Cause:

Action:

OGGV-00132
Client error. ("{0}").

Category:
Other

Cause:

Action:

OGGV-00133
RunId ({0}, {1}, {2}) does not exist.

Category:
Other

Cause:

Action:

OGGV-00134
Job "{0}" is already running as ({1}, {2}, {3}).

Category:
Other

Cause:

Action:

OGGV-00135
Job "{0}" is still running, cannot delete a running job.

Category:
Other

Cause:

Action:

OGGV-00136
Job cannot be run. Check server config parameters server.max_concurrent_jobs and server.max_concurrent_comparision_threads.

Category:
Other

Cause:

Action:

OGGV-00137
{0} "{1}" contains invalid character(s).

Category:
Other

Cause:

Action:

OGGV-00138
Could not create report file "{0}"

Category:
Other

Cause:

Action:

OGGV-00139
Field "{0}" cannot be more than {1} characters "{2}"

Category:
Other

Cause:

Action:

OGGV-00140
"{0}" reading the file "{1}"

Category:
Other

Cause:

Action:

OGGV-00142
Out of Sync details were not saved for this comparison run

Category:
Other

Cause:

Action:

OGGV-00143
Job cannot be run because it contains no compare pairs.

Category:
Other

Cause:

Action:

OGGV-00144
Source column "{0}" not found in source table "{1}"

Category:
Other

Cause:

Action:

OGGV-00145
Source column "{0}" has datatype "{1}", the datatype does not match the source table datatype of "{2}"

Category:
Other

Cause:

Action:

OGGV-00146
Target column "{0}" not found in target table "{1}"

Category:
Other

Cause:

Action:

OGGV-00147
Target column "{0}" has datatype "{1}", the datatype does not match the target table datatype of "{2}"

Category:
Other

Cause:

Action:

OGGV-00148
The number of source columns doesn"t match the number of target columns

Category:
Other

Cause:

Action:

OGGV-00149
The datatype of source column "{0}" ({1}) does not match the datatype of target column "{2}" ({3})

Category:
Other

Cause:

Action:

OGGV-00150
Source table "{0}" does not exist

Category:
Other

Cause:

Action:

OGGV-00151
Target table "{0}" does not exist

Category:
Other

Cause:

Action:

OGGV-00152
Source index "{0}" does not exist

Category:
Other

Cause:

Action:

OGGV-00153
Target index "{0}" does not exist

Category:
Other

Cause:

Action:

OGGV-00154
The number of source key columns ({0}) does not match the actual number of columns ({1}) of index "{2}"

Category:
Other

Cause:

Action:

OGGV-00155
The number of target key columns ({0}) does not match the actual number of columns ({1}) of index "{2}"

Category:
Other

Cause:

Action:

OGGV-00156
Source key column "{0}" is not part of index "{1}"

Category:
Other

Cause:

Action:

OGGV-00157
Target key column "{0}" is not part of index "{1}"

Category:
Other

Cause:

Action:

OGGV-00158
The datatype of source key column "{0}" ({1}) does not match the datatype of the same column in index "{2}" ({3})

Category:
Other

Cause:

Action:

OGGV-00159
The datatype of target key column "{0}" ({1}) does not match the datatype of the same column in index "{2}" ({3})

Category:
Other

Cause:

Action:

OGGV-00160
The number of source keys columns is different than the number of target key columns

Category:
Other

Cause:

Action:

OGGV-00161
The datatype of source key column "{0}" ({1}) does not match the datatype of target key column "{2}" ({3})

Category:
Other

Cause:

Action:

OGGV-00162
Index validation failed because there were no mappable columns.

Category:
Other

Cause:

Action:

OGGV-00163
Enscribe compare pair "{0}" cannot be executed because it has user defined keys and sorting is not done in the server.

Category:
Other

Cause:

Action:

OGGV-00164
Enscribe compare pair "{0}" cannot be executed because the Confirm Out Of Sync step is on.

Category:
Other

Cause:

Action:

OGGV-00165
NSK compare pair "{0}" cannot be executed because it has delta processing enabled and sorting is not done in the server.

Category:
Other

Cause:

Action:

OGGV-00166
NSK Enscribe compare pair "{0}" cannot be executed because it has starting/ending key range(s) when sorting is done in the server.

Category:
Other

Cause:

Action:

OGGV-00167
NSK SQL/MP compare pair "{0}" cannot be executed because it has SQL predicate(s) when sorting is done in the server.

Category:
Other

Cause:

Action:

OGGV-00168
The comparison format of source column "{0}" ({1}) cannot convert to the comparison of target column "{2}" ({3}).

Category:
Other

Cause:

Action:

OGGV-00169
Source column "{0}": Agent does not support a comparison format "{1}" for datatype "{2}".

Category:
Other

Cause:

Action:

OGGV-00170
Source column "{0}": {1} of {2} is greater than the max of {3}.

Category:
Other

Cause:

Action:

OGGV-00171
Source column "{0}": Agent format "{1}" does not support "{2}".

Category:
Other

Cause:

Action:

OGGV-00172
Source column "{0}" and target column "{1}": "{2}" is mismatched ({3} and {4}).

Category:
Other

Cause:

Action:

OGGV-00173
The comparison format of source key column "{0}" ({1}) cannot convert to the comparison format of target key column "{2}" ({3}).

Category:
Other

Cause:

Action:

OGGV-00174
The {0} table info is missing the "{1}" attribute.

Category:
Other

Cause:

Action:

OGGV-00176
Compare pair "{0}" has empty user defined key columns.

Category:
Other

Cause:

Action:

OGGV-00177
Column was not validated.

Category:
Other

Cause:

Action:

OGGV-00178
Column mapping is valid.

Category:
Other

Cause:

Action:

OGGV-00179
The connection type of "{0}" cannot be changed to "{1}".

Category:
Other

Cause:

Action:

OGGV-00180
The {0} connection type of group "{1}" cannot be changed to "{2}".

Category:
Other

Cause:

Action:

OGGV-00181
The {0} connection type of job "{1}" must match the {2} connection types of all included groups.

Category:
Other

Cause:

Action:

OGGV-00182
Manager at {0}:{1} is not supported because: {2}.

Category:
Other

Cause:

Action:

OGGV-00183
Internal Error: RunJobModify failed with: {0}

Category:
Other

Cause:

Action:

OGGV-00184
Error message: {0}.

Category:
Other

Cause:

Action:

OGGV-00185
SAX Exception: {0}.

Category:
Other

Cause:

Action:

OGGV-00186
Sorting failed with an IO error: {0}

Category:
Other

Cause:

Action:

OGGV-00187
Sorting failed for an unknown reason: {0}

Category:
Other

Cause:

Action:

OGGV-00188
Requested sort memory size, {0}m, too large; sort memory set to {1}m

Category:
Other

Cause:

Action:

OGGV-00189
Total sort memory is {0}m

Category:
Other

Cause:

Action:

OGGV-00190
Requested Maximum comparison memory, {0}m, cannot exceed total memory size; maximum comparison memory is set to {1}m

Category:
Other

Cause:

Action:

OGGV-00191
Maximum comparison memory is {0}m

Category:
Other

Cause:

Action:

OGGV-00192
The requested comparison memory {0}m exceeds the configured maximum {1}m

Category:
Other

Cause:

Action:

OGGV-00193
The memory request waiting threshold, {0}, has been exceeded

Category:
Other

Cause:

Action:

OGGV-00194
The maximum number of concurrent writes is {0}

Category:
Other

Cause:

Action:

OGGV-00195
The maximum number of concurrent reads is {0}

Category:
Other

Cause:

Action:

OGGV-00196
Agent DBMS type changed: was {0} but is now {1}

Category:
Other

Cause:

Action:

OGGV-00197
Partition "{0}" was not found.

Category:
Other

Cause:

Action:

OGGV-00198
{0} Repair Agent failure "{1}"

Category:
Other

Cause:

Action:

OGGV-00199
Repair is not supported by connection "{0}"

Category:
Other

Cause:

Action:

OGGV-00200
Nothing selected for repair

Category:
Other

Cause:

Action:

OGGV-00201
Delta partition name mismatch for {0}

Category:
Other

Cause:

Action:

OGGV-00203
Delta partition physical name mismatch for {0}

Category:
Other

Cause:

Action:

OGGV-00204
Delta processing partition count mismatch for {0}

Category:
Other

Cause:

Action:

OGGV-00205
Source Reader should have completed

Category:
Other

Cause:

Action:

OGGV-00206
Comparison threads did not stop

Category:
Other

Cause:

Action:

OGGV-00207
Repair cannot be executed with Check Update Values set to 'true' when initial comparison skipped the COOS step.

Category:
Other

Cause:

Action:

OGGV-00208
Repair cannot be executed because the Out-Of-Sync file cannot be opened.

Category:
Other

Cause:

Action:

OGGV-00209
Use Secure Socket Layer (SSL) for agent-server communication

Category:
Other

Cause:

Action:

OGGV-00210
Error in communicating with the Agent.

Category:
Other

Cause:

Action:

OGGV-00211
Could not find component {0}

Category:
Other

Cause:

Action:

OGGV-00212
Exception Stack Trace

Category:
Other

Cause:

Action:

OGGV-00213
Missing Item Type: {0}, Missing Item Name: {1}

Category:
Other

Cause:

Action:

OGGV-00214
MethodNotFoundException, coding error

Category:
Other

Cause:

Action:

OGGV-00215
{0} is Null

Category:
Other

Cause:

Action:

OGGV-00216
Unknown Item Type: {0}, Unknown Item Name:{1}

Category:
Other

Cause:

Action:

OGGV-00217
Unable to proceed because {0}

Category:
Other

Cause:

Action:

OGGV-00218
Duplicate {0}: {1}: {2}: {3}

Category:
Other

Cause:

Action:

OGGV-00219
{0} does not support {1}

Category:
Other

Cause:

Action:

OGGV-00220
{0} has unexpected status {1}

Category:
Other

Cause:

Action:

OGGV-00221
The job run did not finish yet

Category:
Other

Cause:

Action:

OGGV-00222
Could not execute {0}

Category:
Other

Cause:

Action:

OGGV-00223
Error when dropping tables: {0}

Category:
Other

Cause:

Action:

OGGV-00224
Unable to make a datasource connection using {0}

Category:
Other

Cause:

Action:

OGGV-00225
Executing {0} requires {1} role

Category:
Other

Cause:

Action:

OGGV-00226
Profile/run option {0}(value : {1}) is incompatible with option {2}(value : {3})

Category:
Other

Cause:

Action:

OGGV-00227
Error occurs when running repair job automatically after compare job, error code: {0} error message: {1}

Category:
Other

Cause:

Action:

OGGV-00228
Compare pair "{0}" already exists

Category:
Other

Cause:

Action:

OGGV-00229
Group "{0}" already exists

Category:
Other

Cause:

Action:

OGGV-00230
Job "{0}" already exists

Category:
Other

Cause:

Action:

OGGV-00231
Profile "{0}" already exists

Category:
Other

Cause:

Action:

OGGV-00232
Error reading file header in "{0}"

Category:
Other

Cause:

Action:

OGGV-00233
Invalid port number: {0}.

Category:
Other

Cause:

Action:

OGGV-00234
Group "{0}" still referenced, you cannot delete it.

Category:
Other

Cause:

Action:

OGGV-00235
Profile "{0}" still referenced, you cannot delete it.

Category:
Other

Cause:

Action:

OGGV-00236
Compare pair "{0}" does not exist

Category:
Other

Cause:

Action:

OGGV-00237
Group "{0}" does not exist

Category:
Other

Cause:

Action:

OGGV-00238
Job "{0}" does not exist

Category:
Other

Cause:

Action:

OGGV-00239
Profile "{0}" does not exist

Category:
Other

Cause:

Action:

OGGV-00240
Target column "{0}": Agent does not support a comparison format "{1}" for datatype "{2}".

Category:
Other

Cause:

Action:

OGGV-00241
Target column "{0}": {1} of {2} is greater than the max of {3}.

Category:
Other

Cause:

Action:

OGGV-00242
Target column "{0}": Agent format "{1}" does not support "{2}".

Category:
Other

Cause:

Action:

OGGV-00243
Target Reader should have completed

Category:
Other

Cause:

Action:

OGGV-00244
The Group referenced no longer exists.

Category:
Other

Cause:

Action:

OGGV-00245
The Job referenced no longer exists.

Category:
Other

Cause:

Action:

OGGV-00301
The Source Table is required.

Category:
Other

Cause:

Action:

OGGV-00302
The Target Table is required.

Category:
Other

Cause:

Action:

OGGV-00303
The Source Schema is required.

Category:
Other

Cause:

Action:

OGGV-00304
The Target Schema is required.

Category:
Other

Cause:

Action:

OGGV-00501
Connection IO exception: {0}

Category:
Other

Cause:

Action:

OGGV-00502
Unable to perform mapping validation. Please select at least one compare pair.

Category:
Other

Cause:

Action:

OGGV-00503
Source row null for {0}

Category:
Other

Cause:

Action:

OGGV-00504
Un-Registered Veridata MBean : {0}

Category:
Other

Cause:

Action:

OGGV-00505
There is already a compare pair named "{0}" in group "{1}"

Category:
Other

Cause:

Action:

OGGV-00506
Compare pair with id {0} does not exist in group "{1}"

Category:
Other

Cause:

Action:

OGGV-00507
"{0}" creating directory "{1}"

Category:
Other

Cause:

Action:

OGGV-00508
Delta partition key mismatch for {0}

Category:
Other

Cause:

Action:

OGGV-00509
Delta Processing can not be enabled for the Compare Pair - {0}, Go to Edit Column Mapping -> Delta Processing Tab for performing configuration.

Category:
Other

Cause:

Action:

OGGV-00510
Unable to enable Delta Processing, Please select at least one compare pair.

Category:
Other

Cause:

Action:

OGGV-00511
Unable to disable Delta Processing, Please select at least one compare pair.

Category:
Other

Cause:

Action:

OGGV-00512
Delta Processing is already enabled for this Compare Pair - {0}

Category:
Other

Cause:

Action:

OGGV-00513
Delta Processing is already disabled for this Compare Pair - {0}

Category:
Other

Cause:

Action:

OGGV-00600
Source row not null for {0}

Category:
Other

Cause:

Action:

OGGV-00601
Error {0} returned from Start ({1})

Category:
Other

Cause:

Action:

OGGV-00602
Empty reply from {0}

Category:
Other

Cause:

Action:

OGGV-00603
IO Exception in exchange state={0}

Category:
Other

Cause:

Action:

OGGV-00604
oosxml file error: Out-Of-Sync counts of any column should not be less than Out-Of-Sync count of key column

Category:
Other

Cause:

Action:

OGGV-00605
Error in parsing chunk: {0}

Category:
Other

Cause:

Action:

OGGV-00606
No veridata.cfg file found: {0}

Category:
Other

Cause:

Action:

OGGV-00607
veridata.cfg failed to load: {0}

Category:
Other

Cause:

Action:

OGGV-00608
VeridataConfig was not initialized.

Category:
Other

Cause:

Action:

OGGV-00609
Read of "{0}" failed: {1}

Category:
Other

Cause:

Action:

OGGV-00610
Could not create sort file on "{0}": {1}

Category:
Other

Cause:

Action:

OGGV-00611
Sort cancelled

Category:
Other

Cause:

Action:

OGGV-00612
Sort cancelled with error: {0}

Category:
Other

Cause:

Action:

OGGV-00613
Error parsing agent response: {0}

Category:
Other

Cause:

Action:

OGGV-00614
XML writer error: {0}

Category:
Other

Cause:

Action:

OGGV-00615
Could not queue cancel request

Category:
Other

Cause:

Action:

OGGV-00616
Could not create Out-Of-Sync file: {0}

Category:
Other

Cause:

Action:

OGGV-00617
OOSXML generation failed: {0}

Category:
Other

Cause:

Action:

OGGV-00618
Could not create directory: {0}

Category:
Other

Cause:

Action:

OGGV-00619
Could not open report file "{0}": {1}

Category:
Other

Cause:

Action:

OGGV-00620
Report write failed: {0}

Category:
Other

Cause:

Action:

OGGV-00621
RowHash agent failed: {0}

Category:
Other

Cause:

Action:

OGGV-00622
Unexpected COOS agent exception: {0}

Category:
Other

Cause:

Action:

OGGV-00623
Exception during COOS cancel agents: {0}

Category:
Other

Cause:

Action:

OGGV-00624
Error trying to save job/group reports: {0}

Category:
Other

Cause:

Action:

OGGV-00625
{0} completed with error: {1}

Category:
Other

Cause:

Action:

OGGV-00626
{0} completed {1} comparisons with {2} Out-Of-Sync

Category:
Other

Cause:

Action:

OGGV-00627
Job "{0}" failed: {1}

Category:
Other

Cause:

Action:

OGGV-00628
Failure during cleanup

Category:
Other

Cause:

Action:

OGGV-00629
In group: "{0}" , repair pair "{1}" completed with error: {2}

Category:
Other

Cause:

Action:

OGGV-00630
Repair job "{0}" failed: {0}

Category:
Other

Cause:

Action:

OGGV-00631
Ignored exception during cancel: {0}

Category:
Other

Cause:

Action:

OGGV-00632
Repair job "{0}" starting

Category:
Other

Cause:

Action:

OGGV-00633
Repair pair "{0}" starting

Category:
Other

Cause:

Action:

OGGV-00635
Cancel complete for {0}

Category:
Other

Cause:

Action:

OGGV-00636
Processing cancel request for {0}

Category:
Other

Cause:

Action:

OGGV-00637
Still waiting for create lock for {0}

Category:
Other

Cause:

Action:

OGGV-00638
Concurrent comparison limit reached

Category:
Other

Cause:

Action:

OGGV-00639
Starting comparison: {0}

Category:
Other

Cause:

Action:

OGGV-00640
Comparison "{0}" is complete

Category:
Other

Cause:

Action:

OGGV-00641
First row read

Category:
Other

Cause:

Action:

OGGV-00642
Registered Veridata MBean : [{0}] object Name: {1}

Category:
Other

Cause:

Action:

OGGV-00643
Comparison job "{0}" starting

Category:
Other

Cause:

Action:

OGGV-00644
Comparison job "{0}" Complete

Category:
Other

Cause:

Action:

OGGV-00645
Available sort memory is {0}

Category:
Other

Cause:

Action:

OGGV-00646
Available processors are: {0}

Category:
Other

Cause:

Action:

OGGV-00647
Repair pair "{0}" is complete

Category:
Other

Cause:

Action:

OGGV-00648
Number of sort threads: {0}

Category:
Other

Cause:

Action:

OGGV-00649
Attempt to send invalid input

Category:
Other

Cause:

Action:

OGGV-00650
CSRF Token is missing or not matching with authorized Session

Category:
Other

Cause:

Action:

OGGV-00651
Config parameter "truncate_spaces_len" accepts values of 0 or 1, ignoring "{0}"

Category:
Other

Cause:

Action:

OGGV-00652
Not running {0} because {1}

Category:
Other

Cause:

Action:

OGGV-00653
No ComparePairs of selection have out-of-sync in previous run or No previous stats available to generate oosxml for Job: {0}

Category:
Other

Cause:

Action:

OGGV-00654
Encryption bits "server.encryption.bits" is limited to {0} by the JRE.

Category:
Other

Cause:

Action:

OGGV-00655
Encryption of report failed "{0}" with: {1}

Category:
Other

Cause:

Action:

OGGV-00657
Report manager failed to start with: {0}

Category:
Other

Cause:

Action:

OGGV-00658
Encryption bits "server.encryption.bits" is required and must be a decimal number

Category:
Other

Cause:

Action:

OGGV-00659
Rolling report encryption key.

Category:
Other

Cause:

Action:

OGGV-00660
Could not allocate mapped memory for sorting. Using heap memory: {0}

Category:
Other

Cause:

Action:

OGGV-00662
Target row not null for {0}

Category:
Other

Cause:

Action:

OGGV-00663
Target row null for {0}

Category:
Other

Cause:

Action:

OGGV-00664
File vdtdomain.cfg was not found : {0}

Category:
Other

Cause:

Action:

OGGV-00665
Current changes in the column mapping affects Source Delta Column configuration, Please disable delta processing , complete and save column mapping , then select delta columns from the delta processing tab.

Category:
Other

Cause:

Action:

OGGV-00666
Current changes in the column mapping affects Target Delta Column configuration, Please disable delta processing , complete and save column mapping , then select delta columns from the delta processing tab.

Category:
Other

Cause:

Action:

OGGV-00667
Delta Column Validation Error.

Category:
Other

Cause:

Action:

OGGV-00668
The Veridata Server version {0} is lower than the minimum repository version {1}

Category:
Other

Cause:

Action:

OGGV-00669
The Veridata repository version {0} is lower than the minimum version required by the Veridata Server {1}

Category:
Other

Cause:

Action:

OGGV-00670
Veridata repository connection started with repository version {0}

Category:
Other

Cause:

Action:

OGGV-00671
Veridata repository connection started. The expected repository version is {0} and the actual version is {1}

Category:
Other

Cause:

Action:

OGGV-00673
Repair after compare is not supported for this Job. Please revisit the Profile settings for this Job or uncheck the repair after compare checkbox from Override run options.

Category:
Other

Cause:

Action:

OGGV-5002
Invalid connection name "{0}" is assigned to Group

Category:
Other

Cause:

Action:

OGGV-20001
Command line flag "{0}" is obsolete.

Category:
Other

Cause:

Action:

OGGV-20002
{0} requires a {1}

Category:
Other

Cause:

Action:

OGGV-20003
Error reading number "{0}"

Category:
Other

Cause:

Action:

OGGV-20004
{0} not allowed with {1}

Category:
Other

Cause:

Action:

OGGV-20005
{0} already specified.

Category:
Other

Cause:

Action:

OGGV-20006
Unrecognized command line flag "{0}"

Category:
Other

Cause:

Action:

OGGV-20007
You must specify -job.

Category:
Other

Cause:

Action:

OGGV-20008
{0} has been deprecated and will be ignored

Category:
Other

Cause:

Action:

OGGV-20009
Run job command line flags require -job or -j

Category:
Other

Cause:

Action:

OGGV-20010
-g requires -c.

Category:
Other

Cause:

Action:

OGGV-20011
-c requires -g.

Category:
Other

Cause:

Action:

OGGV-20012
-rd0 and -rdN require -c.

Category:
Other

Cause:

Action:

OGGV-20013
You cannot specify ascii/hex keys for SQL tables

Category:
Other

Cause:

Action:

OGGV-20014
-rN requires a number greater than 0

Category:
Other

Cause:

Action:

OGGV-20016
The finished stats for record "{0}" could not be found

Category:
Other

Cause:

Action:

OGGV-20017
Could not start the vericom asynchronously

Category:
Other

Cause:

Action:

OGGV-20018
Job "{0}" not found

Category:
Other

Cause:

Action:

OGGV-20019
Group "{0}" not found

Category:
Other

Cause:

Action:

OGGV-20020
Compare pair "{0}" not found

Category:
Other

Cause:

Action:

OGGV-20021
Profile "{0}" not found

Category:
Other

Cause:

Action:

OGGV-20022
The job {0} is already running with runId {1}

Category:
Other

Cause:

Action:

OGGV-20023
Job {0} started

Category:
Other

Cause:

Action:

OGGV-20024
Run ID: {0}

Category:
Other

Cause:

Action:

OGGV-20025
No Job Stats found

Category:
Other

Cause:

Action:

OGGV-20026
Number of Compare Pairs: {0}

Category:
Other

Cause:

Action:

OGGV-20027
Number of Compare Pairs With Errors: {0}

Category:
Other

Cause:

Action:

OGGV-20028
Number of Compare Pairs With No Out-Of-Sync: {0}

Category:
Other

Cause:

Action:

OGGV-20029
Number of Compare Pairs Cancelled: {0}

Category:
Other

Cause:

Action:

OGGV-20030
Job Report Filename: {0}

Category:
Other

Cause:

Action:

OGGV-20031
Compare Pair Report Filename: {0}

Category:
Other

Cause:

Action:

OGGV-20032
Run ID: {0}

Category:
Other

Cause:

Action:

OGGV-20033
Number of Rows Compared: {0}

Category:
Other

Cause:

Action:

OGGV-20034
Number of Rows In Sync: {0}

Category:
Other

Cause:

Action:

OGGV-20035
Number of Rows With Errors: {0}

Category:
Other

Cause:

Action:

OGGV-20036
Number of Rows Out Of Sync: {0}

Category:
Other

Cause:

Action:

OGGV-20037
Compare Pair OOSXML Directory: {0}

Category:
Other

Cause:

Action:

OGGV-20038
Compare Pair OOSXML Filename: {0}

Category:
Other

Cause:

Action:

OGGV-20039
Job Completion Status: {0}

Category:
Other

Cause:

Action:

OGGV-20043
Could not update new repository password.

Category:
Other

Cause:

Action:

OGGV-20044
Error: {0}

Category:
Other

Cause:

Action:

OGGV-20045
Could not validate new repository password.

Category:
Other

Cause:

Action:

OGGV-20046
Could not get Console.

Category:
Other

Cause:

Action:

OGGV-20047
Enter password on the command line instead.

Category:
Other

Cause:

Action:

OGGV-20048
Enter new repository password:

Category:
Other

Cause:

Action:

OGGV-20049
Updated new repository password.

Category:
Other

Cause:

Action:

OGGV-20050
Please visit the [Services->Data Sources->VeridataDataSource] Section in WebLogic Administration console to reset the Veridata Repository Database password. or Please contact System administrator for more information.

Category:
Other

Cause:

Action:

OGGV-20051
Weblogic User Name required.

Category:
Other

Cause:

Action:

OGGV-20052
Weblogic password input failed.

Category:
Other

Cause:

Action:

OGGV-20053
Authorization failed to run commandline tools.

Category:
Other

Cause:

Action:

OGGV-20054
Authentication failed.

Category:
Other

Cause:

Action:

OGGV-20055
Waiting for the Job completion with Polling interval {0} sec

Category:
Other

Cause:

Action:

OGGV-20056
User Interrupted

Category:
Other

Cause:

Action:

OGGV-20057
Number of Repair Pairs: {0}

Category:
Other

Cause:

Action:

OGGV-20058
Number of Repair Pairs With Errors: {0}

Category:
Other

Cause:

Action:

OGGV-20059
Number of Repair Pairs Successfully repaired: {0}

Category:
Other

Cause:

Action:

OGGV-20060
Number of Repair Pairs With Warnings: {0}

Category:
Other

Cause:

Action:

OGGV-20061
Number of Repair Pairs Cancelled: {0}

Category:
Other

Cause:

Action:

OGGV-20062
Repair Job Report Filename: {0}

Category:
Other

Cause:

Action:

OGGV-20063
Repair Job Completion Status: {0}

Category:
Other

Cause:

Action:

OGGV-20064
Repair Run ID: {0}

Category:
Other

Cause:

Action:

OGGV-20065
No out-of-sync comparisons for {0}

Category:
Other

Cause:

Action:

OGGV-20066
You cannot specify SQL partitions for Enscribe

Category:
Other

Cause:

Action:

OGGV-20067
Provided Job does not support Repair operation , Can use "{0}" option to override.

Category:
Other

Cause:

Action:

OGGV-20068
Number of Compare Pairs With Out-Of-Sync: {0}

Category:
Other

Cause:

Action:

OGGV-20069
Could not find veridata.cfg location, property veridata.cfg.loc is null. Make sure veridata.cfg.loc property is specified in the vericom script.

Category:
Other

Cause:

Action:

OGGV-20070
veridata.cfg file does not exist at {0}

Category:
Other

Cause:

Action:

OGGV-20072
Could not find veridata.home location, property veridata.home is null. Make sure veridata.cfg.loc property is specified in the vericom script.

Category:
Other

Cause:

Action:

OGGV-20073
Veridata home folder does not exist at {0}

Category:
Other

Cause:

Action:

OGGV-20075
Property "{0}" is not present or it has wrong value. Please check veridata.cfg file and provide correct value.

Category:
Other

Cause:

Action:

OGGV-20076
Failed to get credentail store location. Please check veridata.cfg file and provide correct value.

Category:
Other

Cause:

Action:

OGGV-20084
Credential store folder "{0}" does not exist.

Category:
Other

Cause:

Action:

OGGV-30000
Expected token: {0}

Category:
Other

Cause:

Action:

OGGV-30002
Replicat filename : {0}

Category:
Other

Cause:

Action:

OGGV-30003
Extract filename : {0}

Category:
Other

Cause:

Action:

OGGV-30004
Uncaught exception

Category:
Other

Cause:

Action:

OGGV-30005
Both host and port must be defined if either is defined for Source

Category:
Other

Cause:

Action:

OGGV-30006
Expression syntax error

Category:
Other

Cause:

Action:

OGGV-30007
Expected assignment source term

Category:
Other

Cause:

Action:

OGGV-30008
Expression evaluation exception : {0}

Category:
Other

Cause:

Action:

OGGV-30009
Missing arguments to function : {0}

Category:
Other

Cause:

Action:

OGGV-30010
Missing or extra arguments to function : {0}

Category:
Other

Cause:

Action:

OGGV-30011
Invalid expression, found : {0}

Category:
Other

Cause:

Action:

OGGV-30012
Trail "{0}" not found

Category:
Other

Cause:

Action:

OGGV-30013
Usage: gg2v [[-noscripting|-create|-replace|-update] -wluser <user> [-wlport <port>]] [-p <propfile>] [-o <out file>] [<extract param file>] <replicat param file> or -help or -version

Category:
Other

Cause:

Action:

OGGV-30015
Operation "{0}" already specified

Category:
Other

Cause:

Action:

OGGV-30016
Unrecognized flag: "{0}"

Category:
Other

Cause:

Action:

OGGV-30017
Replicat parameter file required

Category:
Other

Cause:

Action:

OGGV-30018
-create, -replace, and -update require -wluser

Category:
Other

Cause:

Action:

OGGV-30019
Operation failed: "{0}"

Category:
Other

Cause:

Action:

OGGV-30020
Macro name and parameter name must start with "{0}"

Category:
Other

Cause:

Action:

OGGV-30021
Unknown parameter "{0}", file: {1}, line: {2}

Category:
Other

Cause:

Action:

OGGV-30022
Syntax error "{0}", file: {1}, line: {2}

Category:
Other

Cause:

Action:

OGGV-30023
COLMATCH: unrecognized parameter: {0}

Category:
Other

Cause:

Action:

OGGV-30024
Enter WebLogic user password :

Category:
Other

Cause:

Action:

OGGV-30025
Scripting invocation failed

Category:
Other

Cause:

Action:

OGGV-30026
Scripting successful

Category:
Other

Cause:

Action:

OGGV-30027
The specified extract file "{0}" does not exist

Category:
Other

Cause:

Action:

OGGV-30028
The specified replicat file "{0}" does not exist

Category:
Other

Cause:

Action:

OGGV-30029
The option '-wluser' is required when '-noscripting' option not specified

Category:
Other

Cause:

Action:

OGGV-30030
The option "{0}" requires a value

Category:
Other

Cause:

Action:

OGGV-30031
Both host and port must be defined if either is defined for Target

Category:
Other

Cause:

Action:

OGGV-40000
Authorization to allow execution of commandline tools failed.

Category:
Other

Cause:

Action:

OGGV-40001
Authentication failed.

Category:
Other

Cause:

Action:

OGGV-40002
Weblogic User Name required.

Category:
Other

Cause:

Action:

OGGV-40003
Weblogic password input failed.

Category:
Other

Cause:

Action:

OGGV-40004
{0} requires an argument.

Category:
Other

Cause:

Action:

OGGV-40005
{0} cannot be specified with {1}.

Category:
Other

Cause:

Action:

OGGV-40006
Operation failed with exception: {0}.

Category:
Other

Cause:

Action:

OGGV-40007
Operation completed successfully

Category:
Other

Cause:

Action:

OGGV-40008
OOS files require redirection to a file.

Category:
Other

Cause:

Action:

OGGV-40009
Cannot open {0} for reading.

Category:
Other

Cause:

Action:

OGGV-40010
Cannot open {0} for writing.

Category:
Other

Cause:

Action:

OGGV-40011
{0} does not appear to be an encrypted Veridata report file.

Category:
Other

Cause:

Action:

OGGV-40012
Could not generate a new encryption key, check Veridata Server log for errors.

Category:
Other

Cause:

Action:

OGGV-50001
XML configuration is successful

Category:
Other

Cause:

Action:

OGGV-50002
Enter valid XML file name.

Category:
Other

Cause:

Action:

OGGV-50003
No operation specified. Operation should be [-create|-update|-replace|-delete |-export]

Category:
Other

Cause:

Action:

OGGV-50004
Veridata server is not running. Please start veridata server and rerun the command

Category:
Other

Cause:

Action:

OGGV-50005
Unable to parse xml file

Category:
Other

Cause:

Action:

OGGV-50006
Unable to read config xml file

Category:
Other

Cause:

Action:

OGGV-50007
Enter WebLogic user password :

Category:
Other

Cause:

Action:

OGGV-50008
Error in authenticating with WebLogic, please check the supplied arguments or credentials.

Category:
Other

Cause:

Action:

OGGV-50009
Error in executing the scripting request, please contact system administrator for more information.

Category:
Other

Cause:

Action:

OGGV-50010
Error in reading the supplied xml file.

Category:
Other

Cause:

Action:

OGGV-50011
Unknown error during scripting execution, please contact system administrator for more information.

Category:
Other

Cause:

Action:

OGGV-50012
The supplied WebLogic user does not have required authorization to access command line tools.

Category:
Other

Cause:

Action:

OGGV-50013
Requested Operation : "{0}"

Category:
Other

Cause:

Action:

OGGV-50014
Scripting file name : "{0}"

Category:
Other

Cause:

Action:

OGGV-50015
WebLogic Username : "{0}"

Category:
Other

Cause:

Action:

OGGV-50016
WebLogic Port number: "{0}"

Category:
Other

Cause:

Action:

OGGV-50017
Can not connect to database using connection details "{0}"

Category:
Other

Cause:

Action:

OGGV-50018
Connection with the name "{0}" already exists.

Category:
Other

Cause:

Action:

OGGV-50019
ComparePair validation failed for Group "{0}"

Category:
Other

Cause:

Action:

OGGV-50020
Group with the name "{0}" already exists.

Category:
Other

Cause:

Action:

OGGV-50021
Job with the name "{0}" already exists.

Category:
Other

Cause:

Action:

OGGV-50023
Invalid group "{0}" is assigned to Job

Category:
Other

Cause:

Action:

OGGV-50024
Invalid profile "{0}" is assigned to job

Category:
Other

Cause:

Action:

OGGV-50025
Invalid profile "{0}" is assigned to Compare Pair

Category:
Other

Cause:

Action:

OGGV-50026
Invalid connection name "{0}" is assigned to Job

Category:
Other

Cause:

Action:

OGGV-50027
Source pattern "{0}" is not well formatted

Category:
Other

Cause:

Action:

OGGV-50028
Connection with the name "{0}" does not exist.

Category:
Other

Cause:

Action:

OGGV-50029
Group with the name "{0}" does not exist.

Category:
Other

Cause:

Action:

OGGV-50030
Job with the name "{0}" does not exist.

Category:
Other

Cause:

Action:

OGGV-50031
White spaces are not allowed.

Category:
Other

Cause:

Action:

OGGV-50032
The name "{0}" contains the invalid character "{1}"

Category:
Other

Cause:

Action:

OGGV-50033
Please enter a valid host name

Category:
Other

Cause:

Action:

OGGV-50034
The catalog "{0}" does not exist on the source system

Category:
Other

Cause:

Action:

OGGV-50035
The catalog "{0}" does not exist on the target system

Category:
Other

Cause:

Action:

OGGV-50036
The schema "{0}" does not exist on the source system

Category:
Other

Cause:

Action:

OGGV-50037
The schema "{0}" does not exist on the target system

Category:
Other

Cause:

Action:

OGGV-50038
The source primary key, "{0}", and the target primary key, "{1}", must have the same number of columns

Category:
Other

Cause:

Action:

OGGV-50039
The target primary key, "{0}", requires an index name or a key column list

Category:
Other

Cause:

Action:

OGGV-50040
The source system requires a catalog name for compare pairs

Category:
Other

Cause:

Action:

OGGV-50041
The target system requires a catalog name for compare pairs

Category:
Other

Cause:

Action:

OGGV-50042
The specified index, "{0}", does not exist for table "{1}"

Category:
Other

Cause:

Action:

OGGV-50043
The specified index, "{0}", does not exist for table "{1}"

Category:
Other

Cause:

Action:

OGGV-50044
Unable to create Job "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50045
Unable to create Group "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50046
Unable to create Connection "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50047
Unable to create Compare Pair "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50048
Unable to update Job "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50049
Unable to update Group "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50050
Unable to update Connection "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50051
Unable to update Compare Pair "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50052
Unable to delete Group "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50053
Unable to delete Connection "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50054
Unable to delete Compare Pair "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50055
Connection"{0}" is used by job "{1}"

Category:
Other

Cause:

Action:

OGGV-50056
Connection"{0}" is used by group "{1}"

Category:
Other

Cause:

Action:

OGGV-50057
Group "{0}" is used by job "{1}"

Category:
Other

Cause:

Action:

OGGV-50058
Could not list the existing jobs due to: {0}

Category:
Other

Cause:

Action:

OGGV-50059
Could not list the existing groups due to: {0}

Category:
Other

Cause:

Action:

OGGV-50060
Parsing failed

Category:
Other

Cause:

Action:

OGGV-50061
Error while parsing the XML {0}

Category:
Other

Cause:

Action:

OGGV-50062
Fatal error while parsing the XML {0}

Category:
Other

Cause:

Action:

OGGV-50063
Missing required value for "{0}"

Category:
Other

Cause:

Action:

OGGV-50064
Missing required boolean value for "{0}"

Category:
Other

Cause:

Action:

OGGV-50065
Missing required integer value for "{0}"

Category:
Other

Cause:

Action:

OGGV-50066
Invalid integer value for "{0}"

Category:
Other

Cause:

Action:

OGGV-50067
Deleting jobs

Category:
Other

Cause:

Action:

OGGV-50068
Job "{0}" deleted

Category:
Other

Cause:

Action:

OGGV-50069
Deleting groups

Category:
Other

Cause:

Action:

OGGV-50070
Compare Pair "{0}" deleted

Category:
Other

Cause:

Action:

OGGV-50080
Group "{0}" deleted

Category:
Other

Cause:

Action:

OGGV-50081
Deleting connections

Category:
Other

Cause:

Action:

OGGV-50082
Connection "{0}" deleted

Category:
Other

Cause:

Action:

OGGV-50083
Updating jobs

Category:
Other

Cause:

Action:

OGGV-50084
Job "{0}" updated

Category:
Other

Cause:

Action:

OGGV-50085
Updating groups

Category:
Other

Cause:

Action:

OGGV-50086
Group "{0}" updated

Category:
Other

Cause:

Action:

OGGV-50087
Updating compare pairs for group "{0}"

Category:
Other

Cause:

Action:

OGGV-50088
Compare Pair "{0}" updated

Category:
Other

Cause:

Action:

OGGV-50089
Updating connections

Category:
Other

Cause:

Action:

OGGV-50090
Connection "{0}" updated

Category:
Other

Cause:

Action:

OGGV-50091
Creating jobs

Category:
Other

Cause:

Action:

OGGV-50092
Job "{0}" created

Category:
Other

Cause:

Action:

OGGV-50093
Creating groups

Category:
Other

Cause:

Action:

OGGV-50094
Group "{0}" created

Category:
Other

Cause:

Action:

OGGV-50095
Creating compare pairs for group "{0}"

Category:
Other

Cause:

Action:

OGGV-50096
Compare Pair "{0}" created

Category:
Other

Cause:

Action:

OGGV-50097
Creating connections

Category:
Other

Cause:

Action:

OGGV-50098
Connection "{0}" created

Category:
Other

Cause:

Action:

OGGV-50099
Compare Pair validation failed

Category:
Other

Cause:

Action:

OGGV-50100
Skipping Compare Pair "{0}" due to {1}

Category:
Other

Cause:

Action:

OGGV-50101
Compare Pair "{0}" validation failed due to {1}

Category:
Other

Cause:

Action:

OGGV-50102
Compare Pair "{0}" validation successful

Category:
Other

Cause:

Action:

OGGV-50103
Compare Pair "{0}" has multiple partition on "{1}" side

Category:
Other

Cause:

Action:

OGGV-50105
Exception caught while processing: {0}

Category:
Other

Cause:

Action:

OGGV-50106
Usage: veridata_scripting [-create|-update|-replace|-delete] configxml_fullpath [-wlPort portno] -wlUser commandline_username

Category:
Other

Cause:

Action:

OGGV-50107
Connection with the name "{0}" has a repairUser but does not have repairPassword or it has a repairPassword but does not have repairUser

Category:
Other

Cause:

Action:

OGGV-50108
Waiting for the Scripting task completion with Polling interval {0} sec

Category:
Other

Cause:

Action:

OGGV-50109
User Interrupted

Category:
Other

Cause:

Action:

OGGV-50110
Profile with the name "{0}" already exists.

Category:
Other

Cause:

Action:

OGGV-50111
Profile with the name "{0}" does not exist.

Category:
Other

Cause:

Action:

OGGV-50112
Unable to update profile "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50113
Unable to delete profile "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50114
Could not list the existing profiles due to: {0}

Category:
Other

Cause:

Action:

OGGV-50115
profile"{0}" is used by job "{1}"

Category:
Other

Cause:

Action:

OGGV-50116
profile"{0}" is used by Compare Pair "{1}"

Category:
Other

Cause:

Action:

OGGV-50117
Deleting profiles

Category:
Other

Cause:

Action:

OGGV-50118
Profile "{0}" deleted

Category:
Other

Cause:

Action:

OGGV-50119
Updating profiles

Category:
Other

Cause:

Action:

OGGV-50120
Profile "{0}" updated

Category:
Other

Cause:

Action:

OGGV-50121
Creating profiles

Category:
Other

Cause:

Action:

OGGV-50122
Profile "{0}" created

Category:
Other

Cause:

Action:

OGGV-50123
Invalid boolean value for "{0}". Valid values are true or false.

Category:
Other

Cause:

Action:

OGGV-50124
Invalid boolean value "{0}" for "{1}". Valid values are true or false.

Category:
Other

Cause:

Action:

OGGV-50125
Invalid integer value "{0}" for "{1}"

Category:
Other

Cause:

Action:

OGGV-50126
Invalid value "{0}" for "{1}". See documentation for correct set of values.

Category:
Other

Cause:

Action:

OGGV-50127
Input value "{0}" for "{1}" is less than minimum supported value of "{2}".

Category:
Other

Cause:

Action:

OGGV-50128
Input value "{0}" for "{1}" is more than maximum supported value of "{2}".

Category:
Other

Cause:

Action:

OGGV-50129
The parameter "{0}" is not supported. Please check documentation for correct parameters.

Category:
Other

Cause:

Action:

OGGV-50130
Precision is not supported for "{0}" format.

Category:
Other

Cause:

Action:

OGGV-50131
Scale is not supported for "{0}" format.

Category:
Other

Cause:

Action:

OGGV-50132
Timezone is not supported for "{0}" format.

Category:
Other

Cause:

Action:

OGGV-50133
Timezone "{0}" is invalid or not supported for "{1}" format.

Category:
Other

Cause:

Action:

OGGV-50134
Format "{0}" is invalid or not supported for "{1}" datatype.

Category:
Other

Cause:

Action:

OGGV-50135
Datatype "{0}" is invalid or not supported for "{1}" connection

Category:
Other

Cause:

Action:

OGGV-50137
The Query for the specified source delta column : "{0}" is empty.

Category:
Other

Cause:

Action:

OGGV-50138
Unable to validate delta configuration, There are no valid delta source columns for this compare-pair : "{0}", Group Name : "{1}"

Category:
Other

Cause:

Action:

OGGV-50139
The supplied source delta column : "{0}", is not a suitable delta column. Compare-Pair Name : "{1}" , Group Name : "{2}".

Category:
Other

Cause:

Action:

OGGV-50140
Unable to validate delta configuration, There are no valid delta target columns for this compare-pair : "{0}", Group Name : "{1}"

Category:
Other

Cause:

Action:

OGGV-50141
The supplied target delta column : "{0}", is not a suitable delta column. Compare-Pair Name : "{1}" , Group Name : "{2}".

Category:
Other

Cause:

Action:

OGGV-50142
The supplied target delta column : "{0}", is not a suitable delta column.

Category:
Other

Cause:

Action:

OGGV-50143
Expecting, source delta configuration for this compare-pair : "{0}".

Category:
Other

Cause:

Action:

OGGV-50144
Not expecting, source delta configuration for this compare-pair : "{0}".

Category:
Other

Cause:

Action:

OGGV-50145
Expecting, target delta configuration for this compare-pair : "{0}".

Category:
Other

Cause:

Action:

OGGV-50146
Not expecting, target delta configuration for this compare-pair : "{0}".

Category:
Other

Cause:

Action:

OGGV-50150
{0} requires a {1}

Category:
Other

Cause:

Action:

OGGV-50151
Error reading number "{0}"

Category:
Other

Cause:

Action:

OGGV-50152
{0} not allowed with {1}

Category:
Other

Cause:

Action:

OGGV-50153
{0} already specified.

Category:
Other

Cause:

Action:

OGGV-50154
Unrecognized command line flag "{0}"

Category:
Other

Cause:

Action:

OGGV-50159
Weblogic User Name required.

Category:
Other

Cause:

Action:

OGGV-50160
Remote repository DB schema and User Name required.

Category:
Other

Cause:

Action:

OGGV-50161
File already exist. Overwrite the file? y/[n].

Category:
Other

Cause:

Action:

OGGV-50162
Please re-run the export operation with new valid file or provide permission to overwrite the file.

Category:
Other

Cause:

Action:

OGGV-50163
File does not have write permission. Please provide valid file name.

Category:
Other

Cause:

Action:

OGGV-50164
Enscribe type "{0}" is not valid.

Category:
Other

Cause:

Action:

OGGV-50165
Validating input provided for export.

Category:
Other

Cause:

Action:

OGGV-50166
Boolean value is null. Returning null.

Category:
Other

Cause:

Action:

OGGV-50168
System mapped primary key

Category:
Other

Cause:

Action:

OGGV-50169
System mapped primary key

Category:
Other

Cause:

Action:

OGGV-50170
Failed to connect to repository. Please check the connection details provided.

Category:
Other

Cause:

Action:

OGGV-50171
Test connection to repository is successful.

Category:
Other

Cause:

Action:

OGGV-50172
The connection details provided does not contain veridata tables. Please provide valid veridata repository details and try again.

Category:
Other

Cause:

Action:

OGGV-50173
Could not get datasource from spring context.

Category:
Other

Cause:

Action:

OGGV-50174
Error in getting connection from datasource.

Category:
Other

Cause:

Action:

OGGV-50175
Repository version of exported veridata repository : "{0}".

Category:
Other

Cause:

Action:

OGGV-50176
Processing Jobs

Category:
Other

Cause:

Action:

OGGV-50177
Processing Groups

Category:
Other

Cause:

Action:

OGGV-50178
Processing Connections

Category:
Other

Cause:

Action:

OGGV-50179
Processing Profiles

Category:
Other

Cause:

Action:

OGGV-50180
Generating xml scripting file.

Category:
Other

Cause:

Action:

OGGV-50181
Writing repository configuration to output file: "{0}"

Category:
Other

Cause:

Action:

OGGV-50182
Error while writing configuration to XML file "{0}".

Category:
Other

Cause:

Action:

OGGV-50183
Error while reading configuration XML file "{0}".

Category:
Other

Cause:

Action:

OGGV-50184
Getting repository connection from url provided "{0}".

Category:
Other

Cause:

Action:

OGGV-50185
Getting repository connection from datasource.

Category:
Other

Cause:

Action:

OGGV-50186
Connection list was empty or exporting all connections. No connection name to validate.

Category:
Other

Cause:

Action:

OGGV-50187
Group list was empty or exporting all groups. No group name to validate.

Category:
Other

Cause:

Action:

OGGV-50188
Job list was empty or exporting all jobs. No job name to validate.

Category:
Other

Cause:

Action:

OGGV-50189
Profile list was empty or exporting all profiles. No profile name to validate.

Category:
Other

Cause:

Action:

OGGV-50190
Connection name "{0}" is present in the repository

Category:
Other

Cause:

Action:

OGGV-50191
Connection name "{0}" is not present in the repository

Category:
Other

Cause:

Action:

OGGV-50192
Group name "{0}" is present in the repository

Category:
Other

Cause:

Action:

OGGV-50193
Group name "{0}" is not present in the repository

Category:
Other

Cause:

Action:

OGGV-50194
Job name "{0}" is present in the repository

Category:
Other

Cause:

Action:

OGGV-50195
Job name "{0}" is not present in the repository

Category:
Other

Cause:

Action:

OGGV-50196
Profile name "{0}" is present in the repository

Category:
Other

Cause:

Action:

OGGV-50197
Profile name "{0}" is not present in the repository

Category:
Other

Cause:

Action:

OGGV-50198
Connection option not provided for exporting. Not exporting any independent connection objects.

Category:
Other

Cause:

Action:

OGGV-50199
Group option not provided for exporting. Not exporting any independent group objects.

Category:
Other

Cause:

Action:

OGGV-50200
Job option not provided for exporting. Not exporting any independent job objects.

Category:
Other

Cause:

Action:

OGGV-50201
Profile option not provided for exporting. Not exporting any independent profile objects.

Category:
Other

Cause:

Action:

OGGV-50202
Exporting all connections.

Category:
Other

Cause:

Action:

OGGV-50203
Exporting all groups.

Category:
Other

Cause:

Action:

OGGV-50204
Exporting all jobs.

Category:
Other

Cause:

Action:

OGGV-50205
Exporting all profiles.

Category:
Other

Cause:

Action:

OGGV-50206
Exporting connections present in list.

Category:
Other

Cause:

Action:

OGGV-50207
Exporting groups present in list.

Category:
Other

Cause:

Action:

OGGV-50208
Exporting jobs present in list.

Category:
Other

Cause:

Action:

OGGV-50209
Exporting profiles present in list.

Category:
Other

Cause:

Action:

OGGV-50210
Not exporting any connections.

Category:
Other

Cause:

Action:

OGGV-50211
Not exporting any groups.

Category:
Other

Cause:

Action:

OGGV-50212
Not exporting any profiles.

Category:
Other

Cause:

Action:

OGGV-50213
Exporting connection "{0}".

Category:
Other

Cause:

Action:

OGGV-50214
Exporting group "{0}".

Category:
Other

Cause:

Action:

OGGV-50215
Exporting job "{0}".

Category:
Other

Cause:

Action:

OGGV-50216
Exporting profile "{0}".

Category:
Other

Cause:

Action:

OGGV-50217
Failed to export connections.

Category:
Other

Cause:

Action:

OGGV-50218
Failed to export groups.

Category:
Other

Cause:

Action:

OGGV-50219
Failed to export jobs.

Category:
Other

Cause:

Action:

OGGV-50220
Failed to export profiles.

Category:
Other

Cause:

Action:

OGGV-50221
Jdbc connection URL is null.

Category:
Other

Cause:

Action:

OGGV-50222
The connection url "{0}" is unrecognized. URLs need to start with one of "{1}}".

Category:
Other

Cause:

Action:

OGGV-50223
Jdbc driver class "{0}" not found in the classpath.

Category:
Other

Cause:

Action:

OGGV-50225
NSK file-pattern is not supported with schema wildcard. Please use exact names with file-pattern options.

Category:
Other

Cause:

Action:

OGGV-50226
Connection names.

Category:
Other

Cause:

Action:

OGGV-50227
Group names.

Category:
Other

Cause:

Action:

OGGV-50228
Job names.

Category:
Other

Cause:

Action:

OGGV-50229
Profile names.

Category:
Other

Cause:

Action:

OGGV-50230
Connection names provided by user.

Category:
Other

Cause:

Action:

OGGV-50231
Group names provided by user.

Category:
Other

Cause:

Action:

OGGV-50232
Job names provided by user.

Category:
Other

Cause:

Action:

OGGV-50233
Profile names provided by user.

Category:
Other

Cause:

Action:

OGGV-50234
Argument 'vdtPath' is only for export operation when using external veridata db and using 'exportPassword' argument.

Category:
Other

Cause:

Action:

OGGV-50235
Exporting connections for external veridata db.

Category:
Other

Cause:

Action:

OGGV-50236
Temporary file for connections : "{0}"

Category:
Other

Cause:

Action:

OGGV-50237
External veridata installation path is null. Path is required for exporting password for external veridata installation.

Category:
Other

Cause:

Action:

OGGV-50238
External veridata installation path "{0}" does not exist or is incorrect. Please enter correct path for external veridata installation.

Category:
Other

Cause:

Action:

OGGV-50239
Checking if veridata path is 12c path : "{0}".

Category:
Other

Cause:

Action:

OGGV-50240
Checking if veridata path is 11g path : "{0}".

Category:
Other

Cause:

Action:

OGGV-50241
Path "{0}" does not exist.

Category:
Other

Cause:

Action:

OGGV-50242
Jps file was not found in the path "{0}". Please enter the correct veridata installtion path. It will be domain path for 12c and Installation location for 11g.

Category:
Other

Cause:

Action:

OGGV-50243
Path of jps file is "{0}".

Category:
Other

Cause:

Action:

OGGV-50244
Could not find java.home from system property.

Category:
Other

Cause:

Action:

OGGV-50245
Java home "{0}".

Category:
Other

Cause:

Action:

OGGV-50246
Java home "{0}" does not exist.

Category:
Other

Cause:

Action:

OGGV-50247
Jar file location "{0}".

Category:
Other

Cause:

Action:

OGGV-50248
Failed to export connection password to file.

Category:
Other

Cause:

Action:

OGGV-50249
Using temporary jps config file "{0}" for veridata 11g.

Category:
Other

Cause:

Action:

OGGV-50250
Failed to read passwords from wallet.

Category:
Other

Cause:

Action:

OGGV-50251
Wrong number of arguments passed for wallet export operation.

Category:
Other

Cause:

Action:

OGGV-50252
Wrong argumnet passed "{0}"

Category:
Other

Cause:

Action:

OGGV-50253
The source system requires a schema name for compare pairs

Category:
Other

Cause:

Action:

OGGV-50254
The target system requires a schema name for compare pairs

Category:
Other

Cause:

Action:

OGGV-50255
Veridata path provided "{0}" does not exist.

Category:
Other

Cause:

Action:

OGGV-50256
Veridata path "{0}" should be a directory.

Category:
Other

Cause:

Action:

OGGV-50257
"vdtPath" argument is missing. Exporting password for external Veridata setup requires 'vdtPath' argument as well.

Category:
Other

Cause:

Action:

OGGV-50258
Unable to validate delta configuration, Both Source and Target Delta Queries can not be Null for this compare-pair : "{0}", Group Name : "{1}"

Category:
Other

Cause:

Action:

OGGV-50259
Unable to validate delta configuration, Source Delta Query required for this compare-pair : "{0}", Group Name : "{1}"

Category:
Other

Cause:

Action:

OGGV-50260
Unable to validate delta configuration, Target Delta Query required for this compare-pair : "{0}", Group Name : "{1}"

Category:
Other

Cause:

Action:

OGGV-50261
No operation specified. Operation should be [-export]

Category:
Other

Cause:

Action:

OGGV-50262
No operation specified. Operation should be [-create | -update | -delete | -replace]

Category:
Other

Cause:

Action:

OGGV-50263
Operation "{0}" not allowed for profile "{1}". Only update operation is allowed for default profile.

Category:
Other

Cause:

Action:

OGGV-50264
Target pattern "{0}" is not well formatted

Category:
Other

Cause:

Action:

OGGV-50265
Unable to delete Job "{0}" due to: {1}

Category:
Other

Cause:

Action:

OGGV-50266
Not exporting any jobs.

Category:
Other

Cause:

Action:

OGGV-60001
Veridata Agent Version {0} built on {1} {2}

Category:
Other

Cause:

Action:

OGGV-60002
Veridata Agent running on {1} port {0}

Category:
Other

Cause:

Action:

OGGV-60003
Veridata Agent shutting down on port {0} due to error: {1}

Category:
Other

Cause:

Action:

OGGV-60004
Veridata Agent stopped on port {0}

Category:
Other

Cause:

Action:

OGGV-60005
Could not find the agent properties file "{0}"

Category:
Other

Cause:

Action:

OGGV-60006
Error reading file "{0}": {1}

Category:
Other

Cause:

Action:

OGGV-60007
Character set conversion error: {0}

Category:
Other

Cause:

Action:

OGGV-60008
The database.url property is required.

Category:
Other

Cause:

Action:

OGGV-60009
The database.url "{0}" is unrecognized. URLs need to start with one of "{{1}}".

Category:
Other

Cause:

Action:

OGGV-60010
Starting session {0}

Category:
Other

Cause:

Action:

OGGV-60011
Session {0} stopped

Category:
Other

Cause:

Action:

OGGV-60012
IO Error encountered: {0}

Category:
Other

Cause:

Action:

OGGV-60014
Session: {0}

Category:
Other

Cause:

Action:

OGGV-60015
Missing value for: {0}

Category:
Other

Cause:

Action:

OGGV-60016
Parsing exception: {0}

Category:
Other

Cause:

Action:

OGGV-60017
Parsing warning: {0}

Category:
Other

Cause:

Action:

OGGV-60018
Unexpected type: {0}

Category:
Other

Cause:

Action:

OGGV-60019
Corrupted row encountered: {0}

Category:
Other

Cause:

Action:

OGGV-60020
Record length exceeds bytes remaining in message

Category:
Other

Cause:

Action:

OGGV-60021
Row length exceeds bytes remaining in message

Category:
Other

Cause:

Action:

OGGV-60022
{0} rows updated

Category:
Other

Cause:

Action:

OGGV-60023
user "{0}" connected to "{1}"

Category:
Other

Cause:

Action:

OGGV-60024
Failed to open data source for user {0} (from {1} host)

Category:
Other

Cause:

Action:

OGGV-60025
User "{0}" could not connect to database: {1}

Category:
Other

Cause:

Action:

OGGV-60026
Could not get schemas: {0}

Category:
Other

Cause:

Action:

OGGV-60027
Could not get tables: {0}

Category:
Other

Cause:

Action:

OGGV-60028
Could not get database version: {0}

Category:
Other

Cause:

Action:

OGGV-60029
Could not get metadata for "{0}": {1}

Category:
Other

Cause:

Action:

OGGV-60030
Could not get index metadata for "{0}": {1}

Category:
Other

Cause:

Action:

OGGV-60031
Could not list catalogs: {1}

Category:
Other

Cause:

Action:

OGGV-60032
Could not execute statement <{0}>: {1}

Category:
Other

Cause:

Action:

OGGV-60033
Table "{0}" not found

Category:
Other

Cause:

Action:

OGGV-60034
Could not convert value to a String: {0}

Category:
Other

Cause:

Action:

OGGV-60035
Could not convert value to a number: {0}

Category:
Other

Cause:

Action:

OGGV-60036
Could not get type info: {0}

Category:
Other

Cause:

Action:

OGGV-60038
Database query failed: "{1}" SQL<{0}>

Category:
Other

Cause:

Action:

OGGV-60039
COOS lookup query failed: "{1}" SQL<{0}>

Category:
Other

Cause:

Action:

OGGV-60040
The specified transaction isolation level, "{0}", is not recognized

Category:
Other

Cause:

Action:

OGGV-60041
The specified transaction isolation level, "{0}", is not support for {1} databases

Category:
Other

Cause:

Action:

OGGV-60042
The length of column "{0}", {1}, exceeds the supported maximum length, {2}

Category:
Other

Cause:

Action:

OGGV-60043
The display value of hash column "{0}" was truncated to {1} bytes

Category:
Other

Cause:

Action:

OGGV-60044
An unexpected exception has occurred: {0}

Category:
Other

Cause:

Action:

OGGV-60046
A catalog is required

Category:
Other

Cause:

Action:

OGGV-60047
Starting source initial compare for {0}

Category:
Other

Cause:

Action:

OGGV-60048
Database metadata request failed: {0}

Category:
Other

Cause:

Action:

OGGV-60049
Could not load database driver "{0}"

Category:
Other

Cause:

Action:

OGGV-60050
The connection cache property "{0}" has been set to "{1}".

Category:
Other

Cause:

Action:

OGGV-60051
You must login before getting "{0}"

Category:
Other

Cause:

Action:

OGGV-60052
Comparison format "{0}" is not supported on "{1}"

Category:
Other

Cause:

Action:

OGGV-60053
Repair fetch query failed: "{1}" SQL<{0}>

Category:
Other

Cause:

Action:

OGGV-60054
Lookup failed during apply: "{0}"

Category:
Other

Cause:

Action:

OGGV-60055
Fetch of long varchar/varbinary returned 0 rows.

Category:
Other

Cause:

Action:

OGGV-60056
Repair apply failed: "{0}"

Category:
Other

Cause:

Action:

OGGV-60058
Unexpected tag: {0}

Category:
Other

Cause:

Action:

OGGV-60059
Could not configure XML output: {0}

Category:
Other

Cause:

Action:

OGGV-60060
The side, "{0}", specified in the request does not match the side specified in the login request

Category:
Other

Cause:

Action:

OGGV-60063
Ignoring conversion exception: {0}

Category:
Other

Cause:

Action:

OGGV-60064
Duplicate key found

Category:
Other

Cause:

Action:

OGGV-60065
Caught unexpected SQL exception: {0} retry= {1}

Category:
Other

Cause:

Action:

OGGV-60066
CLOB I/O error: {0}

Category:
Other

Cause:

Action:

OGGV-60067
Error freeing temporary CLOB: {}

Category:
Other

Cause:

Action:

OGGV-60068
Could not set the Session Time Zone to {0}

Category:
Other

Cause:

Action:

OGGV-60069
Ignoring invalid database hint: {0}

Category:
Other

Cause:

Action:

OGGV-60070
Character encoding exception: {0}

Category:
Other

Cause:

Action:

OGGV-60071
SQLException was ignored: {0}

Category:
Other

Cause:

Action:

OGGV-60072
Processed {0} rows and waited on full queue: {1} times

Category:
Other

Cause:

Action:

OGGV-60073
JDBC Driver version: {0}

Category:
Other

Cause:

Action:

OGGV-60074
Request was unexpectedly interrupted

Category:
Other

Cause:

Action:

OGGV-60075
OGGV-60152

Category:
Other

Cause:

Action:

OGGV-60076
Cannot parse the database exception error code "{0}", expecting integer

Category:
Other

Cause:

Action:

OGGV-60077
Type name "{0}" java.sql.Types value "{1}" defaulting to BLOB type

Category:
Other

Cause:

Action:

OGGV-60078
Repair apply failed: code: {0}, msg: "{1}"

Category:
Other

Cause:

Action:

OGGV-60079
Disable triggers requires replication role

Category:
Other

Cause:

Action:

OGGV-60080
Could not get position for column "{0}" in table "{1}" for index "{2}"

Category:
Other

Cause:

Action:

OGGV-60150
Configuring logging.

Category:
Other

Cause:

Action:

OGGV-60151
Config file for logger is {0}

Category:
Other

Cause:

Action:

OGGV-60153
Expected {0} type to be {1}

Category:
Other

Cause:

Action:

OGGV-60154
SQL exception occurred during UDT lookup of {0}, msg: {1}

Category:
Other

Cause:

Action:

OGGV-60155
Field {0} not found in UDT {1}

Category:
Other

Cause:

Action:

OGGV-60156
Field {0} expected type {1}, got {2}

Category:
Other

Cause:

Action:

OGGV-60157
Field {0} was missing value.

Category:
Other

Cause:

Action:

OGGV-60158
Unable to serialize: {0}, msg: {1}

Category:
Other

Cause:

Action:

OGGV-60159
Unable to deserialize: {0}, msg: {1}

Category:
Other

Cause:

Action:

OGGV-60160
Connection changed in UDT description

Category:
Other

Cause:

Action:

OGGV-60161
Shutdown request complete: {0}

Category:
Other

Cause:

Action:

OGGV-60162
Reset log request complete: {0}

Category:
Other

Cause:

Action:

OGGV-60163
Agent communications error: {0}

Category:
Other

Cause:

Action:

OGGV-60164
Query to get the delta-base value, failed: "{1}" SQL<{0}>

Category:
Other

Cause:

Action:

OGGV-60165
Invalid delta-base value-query, result set.

Category:
Other

Cause:

Action:

OGGV-60166
No valid rows on delta base value-query, result set.

Category:
Other

Cause:

Action:

OGGV-60167
More than one rows in delta base value-query, result set.

Category:
Other

Cause:

Action:

OGGV-60168
More than one column in delta base value-query, result set.

Category:
Other

Cause:

Action:

OGGV-60169
More than one result-set in delta base value-query, result.

Category:
Other

Cause:

Action:

OGGV-60170
Unable to get the delta base value from the query.

Category:
Other

Cause:

Action:

OGGV-60171
Unable to convert Oracle number {1}

Category:
Other

Cause:

Action:

OGGV-60172
{0} rows deleted

Category:
Other

Cause:

Action:

OGGV-60173
{0} rows inserted

Category:
Other

Cause:

Action:

OGGV-70001
**** Creation of Veridata User Started ****

Category:
Other

Cause:

Action:

OGGV-70002
Database type : {0}

Category:
Other

Cause:

Action:

OGGV-70003
Database connect url : {0}

Category:
Other

Cause:

Action:

OGGV-70004
Database jdbc driver : {0}

Category:
Other

Cause:

Action:

OGGV-70005
Database dba user : {0}

Category:
Other

Cause:

Action:

OGGV-70006
Database schema user : {0}

Category:
Other

Cause:

Action:

OGGV-70007
RCU home path : {0}

Category:
Other

Cause:

Action:

OGGV-70008
Log path location : {0}

Category:
Other

Cause:

Action:

OGGV-70009
Changed MySQL URL : {0}

Category:
Other

Cause:

Action:

OGGV-70010
RCU Connection url : {0}

Category:
Other

Cause:

Action:

OGGV-70011
RCU Connection user : {0}

Category:
Other

Cause:

Action:

OGGV-70012
RCU Connection passed is null

Category:
Other

Cause:

Action:

OGGV-70013
**** Successfully created Veridata User and Database ****

Category:
Other

Cause:

Action:

OGGV-70014
*** Insertion of data into Veridata repository started ****

Category:
Other

Cause:

Action:

OGGV-70015
**** Successfully Inserted data into Veridata Repository ****

Category:
Other

Cause:

Action:

OGGV-70016
*** Deletion of Veridata repository started ****

Category:
Other

Cause:

Action:

OGGV-70017
**** Successfully deleted Veridata Repository ****

Category:
Other

Cause:

Action:

OGGV-70018
Using rcu log level : {0}

Category:
Other

Cause:

Action:

OGGV-70019
Using default log level {0}

Category:
Other

Cause:

Action:

OGGV-70020
Error in creating Veridata user {0}

Category:
Other

Cause:

Action:

OGGV-70021
Error in creating Veridata database {0}

Category:
Other

Cause:

Action:

OGGV-70022
Unsupported database type {0}

Category:
Other

Cause:

Action:

OGGV-70023
Error in Veridata schema user creation

Category:
Other

Cause:

Action:

OGGV-70024
Error in inserting data into repository

Category:
Other

Cause:

Action:

OGGV-70025
Error in dropping Veridata repository

Category:
Other

Cause:

Action:

OGGV-70026
RCU_LOG_LEVEL invalid level: {0}

Category:
Other

Cause:

Action:

OGGV-70027
File {0} not found on classpath

Category:
Other

Cause:

Action:

OGGV-70028
Error in closing open input stream

Category:
Other

Cause:

Action:

OGGV-70201
Saving file : {0}

Category:
Other

Cause:

Action:

OGGV-70202
Loading file : {0}

Category:
Other

Cause:

Action:

OGGV-70203
Key : {0} not updated

Category:
Other

Cause:

Action:

OGGV-70204
Updating key : "{0}" , value : "{1}"

Category:
Other

Cause:

Action:

OGGV-70205
Found null key

Category:
Other

Cause:

Action:

OGGV-70206
String "{0}" should match pattern "{1}"

Category:
Other

Cause:

Action:

OGGV-70207
Loaded Veridata configuration file : {0}

Category:
Other

Cause:

Action:

OGGV-70208
Error processing Veridata configuration file : {0}

Category:
Other

Cause:

Action:

OGGV-70209
Unknown argument : {0}

Category:
Other

Cause:

Action:

OGGV-70210
Arguments can not be empty.

Category:
Other

Cause:

Action:

OGGV-70211
configureVeridata.(sh/cmd) [-pU<veridata.config.property>=<New Value>] [-redeploy -wluser=<weblogic domain admin username>] [-refreshConfig]

Category:
Other

Cause:

Action:

OGGV-70212
When -redeploy option is specified , Weblogic Domain Administrator user name must be specified in -wluser argument.

Category:
Other

Cause:

Action:

OGGV-70213
Enter the password for WebLogic Domain Administrator user {0} :

Category:
Other

Cause:

Action:

OGGV-70214
Property VERIDATA_ORACLE_HOME not set.

Category:
Other

Cause:

Action:

OGGV-70215
Added key : "{0}", value : "{1}"

Category:
Other

Cause:

Action:

OGGV-70216
Failed to refresh the veridata.cfg file. File was not updated.

Category:
Other

Cause:

Action:

OGGV-70301
{0}

Category:
Other

Cause:

Action:

OGGV-70302
Could not create user {0}.

Category:
Other

Cause:

Action:

OGGV-70303
Could not create database {0}.

Category:
Other

Cause:

Action:

OGGV-70304
Could not install database {0}.

Category:
Other

Cause:

Action:

OGGV-70305
Could not drop database {0}.

Category:
Other

Cause:

Action:

OGGV-70306
Could not remove Veridata from database {0}.

Category:
Other

Cause:

Action:

OGGV-70307
Could not drop user {0}.

Category:
Other

Cause:

Action:

OGGV-70308
Upgrade cannot be done on {0}.

Category:
Other

Cause:

Action:

OGGV-70309
Could not upgrade database {0}.

Category:
Other

Cause:

Action:

OGGV-70310
Failed to retrieve current schema version {0}.

Category:
Other

Cause:

Action:

OGGV-70311
Failed to alter schema for tables {0}

Category:
Other

Cause:

Action:

OGGV-70312
Failed to grant permission for user {0}

Category:
Other

Cause:

Action:

OGGV-70401
Length of arguments that are sent to repository are {0}

Category:
Other

Cause:

Action:

OGGV-70402
WLS domain home argument passed to the patching script is {0}

Category:
Other

Cause:

Action:

OGGV-70403
Veridata config file location: {0}

Category:
Other

Cause:

Action:

OGGV-70404
Database name is either null or not specified in Veridata config file and patching cannot be continued

Category:
Other

Cause:

Action:

OGGV-70405
Database name key from Veridata config file: {0}

Category:
Other

Cause:

Action:

OGGV-70406
Failed to apply repository patch

Category:
Other

Cause:

Action:

OGGV-70407
User terminated the patching operation

Category:
Other

Cause:

Action:

OGGV-70408
Password is missing for database user

Category:
Other

Cause:

Action:

OGGV-70409
You are about to patch the repository and database details are - Database URL :: {0} Database User :: {1} Make sure database backup have taken up before proceeding next steps.

Category:
Other

Cause:

Action:

OGGV-70410
Enter Veridata database repository password:

Category:
Other

Cause:

Action:

OGGV-70411
Veridata repository patching is successful.

Category:
Other

Cause:

Action:

OGGV-70412
JdbcUrl used in datasource xml: {0}

Category:
Other

Cause:

Action:

OGGV-70413
Jdbc driver class used in datasource xml: {0}

Category:
Other

Cause:

Action:

OGGV-70414
DB user used in datasource xml: {0}

Category:
Other

Cause:

Action:

OGGV-70415
Veridata repository patching is failed.

Category:
Other

Cause:

Action:

OGGV-70416
Expected argument is missing, Failed to apply repository patch

Category:
Other

Cause:

Action:

OGGV-80001
Get credential for {0}.{1} failed: {2}

Category:
Other

Cause:

Action:

OGGV-80002
Put credential for {0}.{1} failed: {2}

Category:
Other

Cause:

Action:

OGGV-80003
Create credential for WEB.{0} failed: {1}

Category:
Other

Cause:

Action:

OGGV-80004
Remove credential for {0}.{1} failed: {2}

Category:
Other

Cause:

Action:

OGGV-80005
Update credential for WEB.{0} failed: {1}

Category:
Other

Cause:

Action:

OGGV-80006
Authenticate credential for WEB.{0} failed: {1}

Category:
Other

Cause:

Action:

OGGV-80007
Digest credential failed: {1}

Category:
Other

Cause:

Action:

OGGV-80008
Could not get JpsContextFactory

Category:
Other

Cause:

Action:

OGGV-80009
Could not get JPS Config location

Category:
Other

Cause:

Action:

OGGV-80010
Could not get CredentialStore instance

Category:
Other

Cause:

Action:

OGGV-80011
Could not check if credential exists in wallet

Category:
Other

Cause:

Action:

OGGV-80012
Could not remove all credentials in map: {0}

Category:
Other

Cause:

Action:

OGGV-80013
Could not get repository password.

Category:
Other

Cause:

Action:

OGGV-80014
Could not dump credentials

Category:
Other

Cause:

Action:

OGGV-80015
Could not remove all credentials starting with: {0}

Category:
Other

Cause:

Action:

OGGV-80016
Could not open input stream: {0}

Category:
Other

Cause:

Action:

OGGV-80017
Could not process xml stream.

Category:
Other

Cause:

Action:

OGGV-80018
Wallet messages are installed correctly.

Category:
Other

Cause:

Action:

OGGV-80019
The property {0} has not been set.

Category:
Other

Cause:

Action:

OGGV-80020
Wallet "{0}" does not exist.

Category:
Other

Cause:

Action:

OGGV-80022
Enter Agent Identity Store unlock password:

Category:
Other

Cause:

Action:

OGGV-80023
Enter Agent Identity Store entry password:

Category:
Other

Cause:

Action:

OGGV-80024
Enter Agent Trust Store unlock password:

Category:
Other

Cause:

Action:

OGGV-80025
Agent Wallet not initialized.

Category:
Other

Cause:

Action:

OGGV-80026
Password can not be empty for key : {0}

Category:
Other

Cause:

Action:

OGGV-80027
Invalid Agent KeyStores path configuration.

Category:
Other

Cause:

Action:

OGGV-80028
Copyright (c) 2013, 2015, Oracle and/or its affiliates. All rights reserved.

Category:
Other

Cause:

Action:

OGGV-80029
Veridata Agent SSL Configuration Utility

Category:
Other

Cause:

Action:

OGGV-80030
Notes:

Category:
Other

Cause:

Action:

OGGV-80031
1.This utility reads the configuration from agent configuration properties file.

Category:
Other

Cause:

Action:

OGGV-80032
The agent configuration properties file needs to be updated before executing this script.

Category:
Other

Cause:

Action:

OGGV-80033
2.Enter the Entry and Unlock passwords of the configured key-stores below.

Category:
Other

Cause:

Action:

OGGV-80034
Server Identity Store is empty or no alias names found.

Category:
Other

Cause:

Action:

OGGV-80035
Unable to find any valid alias names in Server Identity Store.

Category:
Other

Cause:

Action:

OGGV-80036
Unable to find agent configuration file : {0}

Category:
Other

Cause:

Action:

OGGV-80037
SSL Configuration of Veridata Agent with agent id : {0} is successful.

Category:
Other

Cause:

Action:

OGGV-80038
Error during SSL configuration, please contact System Administrator for more information.

Category:
Other

Cause:

Action:

OGGV-80039
Log redirected to the file : {0}

Category:
Other

Cause:

Action:

OGGV-80040
Exception stack trace

Category:
Other

Cause:

Action:

OGGV-80041
Cannot get SecureRandom instance: {0}

Category:
Other

Cause:

Action:

OGGV-80042
Unrecognized password encoding.

Category:
Other

Cause:

Action:

OGGV-80043
Error in creating OPSS keystore service.

Category:
Other

Cause:

Action:

OGGV-80044
Could not get VeridataWebIdentityStore

Category:
Other

Cause:

Action:

OGGV-80045
Could not get VeridataWebTrustStore

Category:
Other

Cause:

Action:

OGGV-80046
Could not get VeridataWebSymKeyStore

Category:
Other

Cause:

Action:

OGGV-80047
Cannot find MBservers for domain: {0}

Category:
Other

Cause:

Action:

OGGV-80048
Could not change password

Category:
Other

Cause:

Action:

OGGV-80049
"{0}" removed

Category:
Other

Cause:

Action:

OGGV-80050
Error during wallet export information, please contact System Administrator for more information.

Category:
Other

Cause:

Action:

OGGV-80051
Error during wallet import information, please contact System Administrator for more information.

Category:
Other

Cause:

Action:

OGGV-80052
Exporting Wallet : MapName = {0}, Wallet Key = {1}

Category:
Other

Cause:

Action:

OGGV-80053
Importing Wallet : {0} key : {1}

Category:
Other

Cause:

Action:

OGGV-80054
Wallet {0} complete

Category:
Other

Cause:

Action:

OGGV-80055
{0} Wallet - mapName = {1}

Category:
Other

Cause:

Action:

OGGV-80056
Could not encrypt property

Category:
Other

Cause:

Action:

OGGV-80057
Could not decrypt property

Category:
Other

Cause:

Action:

OGGV-80058
Invalid JPS configuration file location : {0}

Category:
Other

Cause:

Action:

OGGV-80059
Invalid Veridata Wallet Map Name

Category:
Other

Cause:

Action:

OGGV-80060
Invalid Veridata Wallet Store Location Name : {0}

Category:
Other

Cause:

Action:

OGGV-80061
Invalid Veridata Wallet Store Location : {0}

Category:
Other

Cause:

Action:

OGGV-80062
Error during initializing Veridata Wallet Store.

Category:
Other

Cause:

Action:

OGGV-80063
Wallet Store file does not exist : {0}

Category:
Other

Cause:

Action:

OGGV-80064
Error during checking if key exists in wallet.

Category:
Other

Cause:

Action:

OGGV-80065
Error during getPassword in wallet.

Category:
Other

Cause:

Action:

OGGV-80066
Error during Wallet Store Save Operation.

Category:
Other

Cause:

Action:

OGGV-80067
Connection list is empty or null. No password will be exported.

Category:
Other

Cause:

Action:

OGGV-80068
Failed to delete Credential Store.

Category:
Other

Cause:

Action:

OGGV-80069
Failed to create alias for user.

Category:
Other

Cause:

Action:

OGGV-80070
Failed to update alias for user.

Category:
Other

Cause:

Action:

OGGV-80071
Failed to delete alias for user.

Category:
Other

Cause:

Action:

OGGV-80072
Failed to display alias.

Category:
Other

Cause:

Action:

OGGV-80073
Failed to get user for alias.

Category:
Other

Cause:

Action:

OGGV-80074
Failed to get password for alias.

Category:
Other

Cause:

Action:

OGGV-80075
Alias already exist in wallet.

Category:
Other

Cause:

Action:

OGGV-80076
Alias does not exist in wallet.

Category:
Other

Cause:

Action:

OGGV-80077
Credential store already exist at provided location.

Category:
Other

Cause:

Action:

OGGV-80078
Failed to create new wallet.

Category:
Other

Cause:

Action:

OGGV-80079
Failed to create credential store folder.

Category:
Other

Cause:

Action:

OGGV-80080
Jps config file already exist. Provide a new empty directory.

Category:
Other

Cause:

Action:

OGGV-80081
Failed to copy jps config file to credential store folder.

Category:
Other

Cause:

Action:

OGGV-80082
File "{0}" does not exist or is not a file.

Category:
Other

Cause:

Action:

OGGV-80083
Failed to initialize credential store wallet.

Category:
Other

Cause:

Action:

OGGV-500167
Side "{0}" not recognised

Category:
Other

Cause:

Action:

OGGV-600013
Unhandled exception "{0}": {1}

Category:
Other

Cause:

Action:

23
OHS-03506 to OHS-04533

OHS-03506
OHS audit configuration load failed

Category:
Configuration

Cause:

Action:

OHS-03507
OHS audit configuration save failed

Category:
Configuration

Cause:

Action:

OHS-03508
Unable to set Custom Log configuration

Category:
Configuration

Cause:

Action:

OHS-03509
CustomLog configuration is wrong

Category:
Configuration

Cause:

Action:

OHS-03526
Failed to read file {0}, because of {1} exception.

Category:
Configuration

Cause:

Action:

OHS-03570
ThreadLimit may not exceed MaxThreadLimitValue.

Category:
Configuration

Cause:

Action:

OHS-03571
ServerLimit may not exceed MaxServerLimitValue.

Category:
Configuration

Cause:

Action:

OHS-03572
MaxRequestWorkers exceeds range, raise ServerLimit.

Category:
Configuration

Cause:

Action:

OHS-03573
MaxRequestWorkers exceeds range, raise ServerLimit or ThreadPerChild.

Category:
Configuration

Cause:

Action:

OHS-03575
The value of ThreadLimit cannot be less than the value of ThreadsPerChild.

Category:
Configuration

Cause:

Action:

OHS-03576
The value of ThreadsPerChild cannot be greater than the value of ThreadLimit.

Category:
Configuration

Cause:

Action:

OHS-03577
The value of ServerLimit cannot be less than the value of MaxRequestWorkers.

Category:
Configuration

Cause:

Action:

OHS-03578
The value of ServerLimit * ThreadsPerChild cannot be less than the value of MaxRequestWorkers.

Category:
Configuration

Cause:

Action:

OHS-03579
Virtual Host Already Exists

Category:
Configuration

Cause:

Action:

OHS-03580
Not a proper Virtual Host Name

Category:
Configuration

Cause:

Action:

OHS-03581
Error enabling module "{0}" : {1}

Category:
Configuration

Cause:

Action:

OHS-03582
The specified module "{0}" is not installed. Module has to be installed before configuring it.

Category:
Configuration

Cause:

Action:

OHS-03583
Register child MBean api failed

Category:
Configuration

Cause:

Action:

OHS-03584
Proxy Port MBean registration failed

Category:
Configuration

Cause:

Action:

OHS-03585
Audit MBean registration failed

Category:
Configuration

Cause:

Action:

OHS-03586
Parsing error while loading MBeans

Category:
Configuration

Cause:

Action:

OHS-03587
Exception occurred while loading MBeans

Category:
Configuration

Cause:

Action:

OHS-03588
Virtual Host creation failed

Category:
Configuration

Cause:

Action:

OHS-03589
Duplicate virtual host found

Category:
Configuration

Cause:

Action:

OHS-03590
Base Virtual host creation failed

Category:
Configuration

Cause:

Action:

OHS-03594
Unregister of configuration MBeans failed

Category:
Configuration

Cause:

Action:

OHS-03595
Unable to get VH objects from root OHS MBean

Category:
Configuration

Cause:

Action:

OHS-03596
Load wallets failed

Category:
Configuration

Cause:

Action:

OHS-03597
Removal of Virtual Host failed

Category:
Configuration

Cause:

Action:

OHS-03598
Removal of Listen failed while removing VH

Category:
Configuration

Cause:

Action:

OHS-03601
Load failed with IOException

Category:
Configuration

Cause:

Action:

OHS-03602
Module name can not be null

Category:
Configuration

Cause:

Action:

OHS-03604
Unable to find Server Name, Setting it to default AdminServer

Category:
Configuration

Cause:

Action:

OHS-03605
Virtual host MBean registration failed

Category:
Configuration

Cause:

Action:

OHS-03606
The current MPM does not support directive {0}.

Category:
Configuration

Cause:

Action:

OHS-03607
Port {0} for {1} is already in use on machine "{2}".

Category:
Configuration

Cause:

Action:

OHS-03608
No ports for {0} were available for auto-assignment on machine "{1}" in the range {2}-{3}.

Category:
Configuration

Cause:

Action:

OHS-03609
Port {0} for {1} is not valid.

Category:
Configuration

Cause:

Action:

OHS-03610
Error disabling module "{0}" : {1}

Category:
Configuration

Cause:

Action:

OHS-03611
Instance "{0}" is in state "{1}" and cannot be deleted.

Category:
Configuration

Cause:

Action:

OHS-03612
The port value, {0}, has already been used and cannot be configured for {1}.

Category:
Configuration

Cause:

Action:

OHS-03613
The mpm "{0}" is not supported for this platform

Category:
Configuration

Cause:

Action:

OHS-03614
The umask "{0}" is not valid, please provide an octal number less than or equal to 0777.

Category:
Configuration

Cause:

Action:

OHS-03701
Error log configuration not valid

Category:
Configuration

Cause:

Action:

OHS-03702
Saving wallet is null

Category:
Configuration

Cause:

Action:

OHS-03703
P12 Wallet is null; Possibly because the wallet is absent/not configured.

Category:
Configuration

Cause:

Action:

OHS-03704
CWallet is null, not able to load cwallet

Category:
Configuration

Cause:

Action:

OHS-03705
Directive does not exist

Category:
Configuration

Cause:

Action:

OHS-03707
WLHost not configured; Illegal Usage

Category:
Configuration

Cause:

Action:

OHS-03708
WLCluster not configured; Not allowed to call listWLCluster

Category:
Configuration

Cause:

Action:

OHS-03709
DynamicServerList is not configured ; Illegal Usage

Category:
Configuration

Cause:

Action:

OHS-03710
SSLCARevocationPath is not configured

Category:
Configuration

Cause:

Action:

OHS-03711
SSLCRLCheck or SSLCARevocationFile is not configured properly

Category:
Configuration

Cause:

Action:

OHS-03712
SSLWallet is not configured properly

Category:
Configuration

Cause:

Action:

OHS-03713
SSLVerifyClient is not configured properly

Category:
Configuration

Cause:

Action:

OHS-03714
SSLCipherSuite is not configured properly

Category:
Configuration

Cause:

Action:

OHS-03715
SSLProtocol is not configured properly

Category:
Configuration

Cause:

Action:

OHS-03716
SSLEngine is not configured properly

Category:
Configuration

Cause:

Action:

OHS-03717
Value cannot start with '#'.

Category:
Configuration

Cause:

Action:

OHS-03718
The file requested, "{0}", is not part of the current OHS configuration. Please enable the file first.

Category:
Configuration

Cause:

Action:

OHS-03719
Cannot register virtual host :

Category:
Configuration

Cause:

Action:

OHS-03720
No virtual host name specified. Invalid virtual host name.

Category:
Configuration

Cause:

Action:

OHS-03721
Default Virtual Host name must be a port number or * or an empty string.

Category:
Configuration

Cause:

Action:

OHS-03722
Virtual Host-Server Name "{0}"-"{1}" already exists.

Category:
Configuration

Cause:

Action:

OHS-03723
Syntax Error in Log configuration: operation failed.

Category:
Configuration

Cause:

Action:

OHS-03724
Could not parse configuration file template value "{0}" on createInstance() invocation.

Category:
Configuration

Cause:

Action:

OHS-03725
Key "{0}" is not a valid configuration file template value on createInstance() invocation.

Category:
Configuration

Cause:

Action:

OHS-03726
Configuration file template value "{0}" does not contain a valid port number on createInstance() invocation.

Category:
Configuration

Cause:

Action:

OHS-03728
Instance name invalid. "{0}" is longer than 30 characters.

Category:
Configuration

Cause:

Action:

OHS-03729
Instance name invalid. "{0}" does not start with a letter.

Category:
Configuration

Cause:

Action:

OHS-03730
Instance name invalid. "{0}" contains an invalid character.

Category:
Configuration

Cause:

Action:

OHS-03731
Instance name invalid :"{0}". The following reserved names (ignoring letter case) are not allowed as instance names : "{1}".

Category:
Configuration

Cause:

Action:

OHS-03732
OHS instance already exists ("{0}").

Category:
Configuration

Cause:

Action:

OHS-03733
OHS instance does not exist ("{0}").

Category:
Configuration

Cause:

Action:

OHS-03734
Invalid port number "{0}" is specified. Port number must be between 1 and 65535 inclusive.

Category:
Configuration

Cause:

Action:

OHS-03735
Invalid log level :"{0}". Valid log levels are : "{1}".

Category:
Configuration

Cause:

Action:

OHS-03736
File {0} could not be read

Category:
Configuration

Cause:

Action:

OHS-03737
Property file {0} could not be loaded; using defaults

Category:
Configuration

Cause:

Action:

OHS-03738
NodeManager is unreachable for the instance "{0}"

Category:
Configuration

Cause:

Action:

OHS-03739
NodeManager is unreachable for the machine "{0}"

Category:
Configuration

Cause:

Action:

OHS-03740
KeepAliveTimeout "{0}" is not valid. Use KeepAliveTimeout num[ms|s|mi|h].

Category:
Configuration

Cause:

Action:

OHS-03741
Specify severity for module "{0}".

Category:
Configuration

Cause:

Action:

OHS-03742
Invalid module "{0}". Only module identifiers specified in LoadModule directives with the trailing _module omitted and statically compiled modules are supported

Category:
Configuration

Cause:

Action:

OHS-03743
OraLogLevel cannot be empty

Category:
Configuration

Cause:

Action:

OHS-03744
Log level "{0}" is not valid.

Category:
Configuration

Cause:

Action:

OHS-03745
LogLevel syntax is not valid. Use LogLevel [module:]level [module:level] ...

Category:
Configuration

Cause:

Action:

OHS-03746
LogLevel cannot be empty

Category:
Configuration

Cause:

Action:

OHS-03747
Log severity "{0}" is not valid.

Category:
Configuration

Cause:

Action:

OHS-03748
OraLogLevel syntax is not valid. Use OraLogLevel [module_name] <msg_type>[:msg_level] ...

Category:
Configuration

Cause:

Action:

OHS-03749
The cipher "{0}" is not valid

Category:
Configuration

Cause:

Action:

OHS-03750
The protocol "{0}" is not valid

Category:
Configuration

Cause:

Action:

OHS-03751
The authentication type "{0}" is not valid

Category:
Configuration

Cause:

Action:

OHS-03752
The crl "{0}" is not valid

Category:
Configuration

Cause:

Action:

OHS-03753
The validation path is not specified

Category:
Configuration

Cause:

Action:

OHS-03754
The wallet is not specified

Category:
Configuration

Cause:

Action:

OHS-03755
VirtualHost copntainer with value "{0}" was not found in the file "{1}".

Category:
Configuration

Cause:

Action:

OHS-03756
There was no "{0}" directive with value "{1}" in the file "{2}".

Category:
Configuration

Cause:

Action:

OHS-03801
Load Operation failed in VH SSLResource

Category:
Configuration

Cause:

Action:

OHS-03802
Load Operation finished in VH SSLResource for instance {0}

Category:
Configuration

Cause:

Action:

OHS-03804
Load operation success for instance {0}

Category:
Configuration

Cause:

Action:

OHS-03805
The specified module "{0}" is already enabled.

Category:
Configuration

Cause:

Action:

OHS-03806
Unregistered all configuration MBeans for instance {0}

Category:
Configuration

Cause:

Action:

OHS-03807
Wildcard char, allow processing

Category:
Configuration

Cause:

Action:

OHS-03808
Error log configuration mode is not apache

Category:
Configuration

Cause:

Action:

OHS-03809
Error log Mode is apache

Category:
Configuration

Cause:

Action:

OHS-03810
Listen Directive not configured

Category:
Configuration

Cause:

Action:

OHS-03811
Listen Directive already exist for specified port

Category:
Configuration

Cause:

Action:

OHS-03814
An error occured while setting the file contents for the config file "{0}". Make sure that the specified configuration file content is of valid format.

Category:
Configuration

Cause:

Action:

OHS-03815
It is not permitted to edit "{0}".

Category:
Configuration

Cause:

Action:

OHS-03816
The specified configuration file "{0}" is not part of the configuration.

Category:
Configuration

Cause:

Action:

OHS-03817
An error occurred setting the contents of config file "{0}": {1}

Category:
Configuration

Cause:

Action:

OHS-03818
An error occurred updating the instance "{0}": {1}

Category:
Configuration

Cause:

Action:

OHS-03819
The specified module "{0}" is already disabled.

Category:
Configuration

Cause:

Action:

OHS-03820
Directory "{0}" is missing from the Oracle HTTP Server installation. The instance cannot be created.

Category:
Configuration

Cause:

Action:

OHS-03821
The ohs.product.home property is not set. The instance cannot be created.

Category:
Configuration

Cause:

Action:

OHS-03822
The fully qualified domain name for host "{0}" could not be resolved. ServerName will be set to "{1}".

Category:
Configuration

Cause:

Action:

OHS-03823
No parameter found on include

Category:
Configuration

Cause:

Action:

OHS-03828
Can not find directive in new DirectiveLine

Category:
Configuration

Cause:

Action:

OHS-03829
Failed to find < in Container directive

Category:
Configuration

Cause:

Action:

OHS-03830
Failed to find space in Container directive

Category:
Configuration

Cause:

Action:

OHS-03831
Failed to find > in Container directive

Category:
Configuration

Cause:

Action:

OHS-03832
IOException reading file

Category:
Configuration

Cause:

Action:

OHS-03833
Never found container terminator for

Category:
Configuration

Cause:

Action:

OHS-03834
Element to add after not found

Category:
Configuration

Cause:

Action:

OHS-03835
Element to add before not found

Category:
Configuration

Cause:

Action:

OHS-03836
Can't find element to remove

Category:
Configuration

Cause:

Action:

OHS-03837
Can't clear the container

Category:
Configuration

Cause:

Action:

OHS-03838
Comment must be empty string or start with #.

Category:
Configuration

Cause:

Action:

OHS-03840
Listen directive corresponding to the address({0}) exists in configuartion file of another instance

Category:
Configuration

Cause:

Action:

OHS-03841
Error while creating the keyStore "{0}".

Category:
Configuration

Cause:

Action:

OHS-03842
Error while deleting the keyStore "{0}".

Category:
Configuration

Cause:

Action:

OHS-03843
Listing KeyStores failed.

Category:
Configuration

Cause:

Action:

OHS-03844
Error while exporting the keyStore "{0}".

Category:
Configuration

Cause:

Action:

OHS-03845
Exporting an empty KeyStore is not allowed, please add certificate(s) before exporting.

Category:
Configuration

Cause:

Action:

OHS-03846
The keystore "{0}" already exists.

Category:
Configuration

Cause:

Action:

OHS-03847
Keystore not associated with any OHS instance.

Category:
Configuration

Cause:

Action:

OHS-03848
The value "{0}" is not valid for the directive "{1}".

Category:
Configuration

Cause:

Action:

OHS-03849
MinSpareThreads cannot be greater than MaxSpareThreads.

Category:
Configuration

Cause:

Action:

OHS-03850
MaxSpareThreads cannot be less than MinSpareThreads.

Category:
Configuration

Cause:

Action:

OHS-03851
Error while creating demo CA-signed certificate.

Category:
Configuration

Cause:

Action:

OHS-03852
Error while importing the contents of a wallet for the instance "{0}".

Category:
Configuration

Cause:

Action:

OHS-03853
The certificates in the wallet "{0}" are not being imported.

Category:
Configuration

Cause:

Action:

OHS-04001
Error while starting the server {0}: server start/stop is already in progress

Category:
Process

Cause:

Action:

OHS-04002
Error while stopping the server {0}: server start/stop is already in progress

Category:
Process

Cause:

Action:

OHS-04003
Graceful stop of server {0} failed

Category:
Process

Cause:

Action:

OHS-04004
Error while restarting the server {0}: server start/stop is already in progress

Category:
Process

Cause:

Action:

OHS-04005
Check the instance log file for more information: {0}

Category:
Process

Cause:

Action:

OHS-04006
Error while restarting the server {0}: server is not currently running

Category:
Process

Cause:

Action:

OHS-04007
Failed to start the server {0} successfully: attempting to cleanup the process

Category:
Process

Cause:

Action:

OHS-04008
Failed to stop the server {0} gracefully: attempting to kill

Category:
Process

Cause:

Action:

OHS-04009
Failed to re-start the server {0} completely: attempting to cleanup the process

Category:
Process

Cause:

Action:

OHS-04010
Server {0} is in an inconsistent state -- the process could not be stopped or killed. This issue must be manually resolved

Category:
Process

Cause:

Action:

OHS-04011
Property file {0} could not be loaded; using defaults

Category:
Process

Cause:

Action:

OHS-04012
Invalid property {0} was configured in file {1}

Category:
Process

Cause:

Action:

OHS-04013
Property {0} has value {1}

Category:
Process

Cause:

Action:

OHS-04014
Property {0} was configured with invalid value {1} in file {2}

Category:
Process

Cause:

Action:

OHS-04015
Invalid instance {0}

Category:
Process

Cause:

Action:

OHS-04016
Failed to start the server {0}

Category:
Process

Cause:

Action:

OHS-04017
Failed to restart the server {0}

Category:
Process

Cause:

Action:

OHS-04018
Starting server {0}

Category:
Process

Cause:

Action:

OHS-04019
Restarting server {0}

Category:
Process

Cause:

Action:

OHS-04020
Stopping server {0}

Category:
Process

Cause:

Action:

OHS-04021
Corrupted value {0} for property

Category:
Process

Cause:

Action:

OHS-04022
File {0} could not be read

Category:
Process

Cause:

Action:

OHS-04023
Invalid property specified: {0}.

Category:
Process

Cause:

Action:

OHS-04024
Valid properties are {0}

Category:
Process

Cause:

Action:

OHS-04025
Invalid value {0} for property {1} specified:

Category:
Process

Cause:

Action:

OHS-04026
Valid values are {0}

Category:
Process

Cause:

Action:

OHS-04027
Valid values are between {0} and {1}

Category:
Process

Cause:

Action:

OHS-04028
Unexpected validator type

Category:
Process

Cause:

Action:

OHS-04029
{0}: command timed out; the process has been terminated

Category:
Process

Cause:

Action:

OHS-04030
{0}: command stdout/stderr IO error

Category:
Process

Cause:

Action:

OHS-04031
Check log file {0}

Category:
Process

Cause:

Action:

OHS-04032
Invalid property environment variable name {0} configured in {1}: {2}. Property environment name syntax is {3}, where {4} is the optional append flag, {5} is the optional numeric order value, and {6} is the name of the environment variable

Category:
Process

Cause:

Action:

OHS-04033
Unable to create SSLSocketFactory

Category:
Process

Cause:

Action:

OHS-04034
SSL is not enabled for the admin port of {0}. Thus, the connection between NodeManager and the admin port of {1} is not secure. SSL must be enabled for this connection. For more information on how to enable SSL for this connection, refer to OHS documentation

Category:
Process

Cause:

Action:

OHS-04035
nm-wallet is not configured for {0} in ohs.plugins.nodemanager.properties. Hence {1} failed to start

Category:
Process

Cause:

Action:

OHS-04036
ServerName directive is not configured in admin.conf of {0}

Category:
Process

Cause:

Action:

OHS-04037
HostName/IP address is not configured for Listen directive in admin.conf of {0}

Category:
Process

Cause:

Action:

OHS-04038
Plugin returns OHS process id as : {0}

Category:
Process

Cause:

Action:

OHS-04039
Force kill was attempted on NULL pid

Category:
Process

Cause:

Action:

OHS-04040
Failed to execute force kill OHS process with cmd : {0}

Category:
Process

Cause:

Action:

OHS-04041
Exception occured while trying to stop stale OHS process

Category:
Process

Cause:

Action:

OHS-04101
Instance {0} already exists

Category:
Process

Cause:

Action:

OHS-04102
InstanceDirectory {0} does not contain a valid OHS instance

Category:
Process

Cause:

Action:

OHS-04103
Unable to delete the directory: {0}

Category:
Process

Cause:

Action:

OHS-04104
Failed to create instance directory: {0}

Category:
Process

Cause:

Action:

OHS-04106
Unable to delete the file: {0}

Category:
Process

Cause:

Action:

OHS-04107
No instance root: {0}

Category:
Process

Cause:

Action:

OHS-04108
Instance {0} is alive; cannot delete

Category:
Process

Cause:

Action:

OHS-04109
Errors occured while commiting changes for the following instances: {0}. Check {1} for details

Category:
Process

Cause:

Action:

OHS-04110
ohs.product.home system property is not set

Category:
Process

Cause:

Action:

OHS-04111
Unable to find a valid OHS installation at {0}

Category:
Process

Cause:

Action:

OHS-04112
Creating instance {0}

Category:
Process

Cause:

Action:

OHS-04113
Deleting instance {0}

Category:
Process

Cause:

Action:

OHS-04114
Updating instance {0}

Category:
Process

Cause:

Action:

OHS-04115
Synchronization copy of {0} to {1} failed

Category:
Process

Cause:

Action:

OHS-04116
Failed to make directory {0}

Category:
Process

Cause:

Action:

OHS-04117
Failed to create file {0}

Category:
Process

Cause:

Action:

OHS-04118
Failed to delete {0}

Category:
Process

Cause:

Action:

OHS-04251
Failed to reach the OHS instance: {0} Make sure that instance is up and running

Category:
Process

Cause:

Action:

OHS-04252
OHS instance failed to respond to the requested URL: {0}

Category:
Process

Cause:

Action:

OHS-04401
Unable to find template directory {0} within OHS installation at {1}. Make sure that {1} contains a valid OHS installation.

Category:
Process

Cause:

Action:

OHS-04402
Unable to copy template directory {0} to directory {1} within new instance

Category:
Process

Cause:

Action:

OHS-04501
Connect to a WebLogic server before using this command.

Category:
Configuration

Cause:

Action:

OHS-04502
Unexpected error: "{0}"

Category:
Configuration

Cause:

Action:

OHS-04503
ohs_createInstance() failed.

Category:
Configuration

Cause:

Action:

OHS-04504
ohs_deleteInstance() failed.

Category:
Configuration

Cause:

Action:

OHS-04505
Machine "{0}" does not exist.

Category:
Configuration

Cause:

Action:

OHS-04506
Instance "{0}" already exists.

Category:
Configuration

Cause:

Action:

OHS-04507
Instance "{0}" is in state "{1}" and cannot be deleted.

Category:
Configuration

Cause:

Action:

OHS-04508
Instance "{0}" does not exist.

Category:
Configuration

Cause:

Action:

OHS-04511
Port {0} is not valid.

Category:
Configuration

Cause:

Action:

OHS-04512
The following arguments are not valid :{0} .

Category:
Configuration

Cause:

Action:

OHS-04513
The following required arguments are missing :{0} .

Category:
Configuration

Cause:

Action:

OHS-04514
Port {0} was specified more than once for the new instance.

Category:
Configuration

Cause:

Action:

OHS-04515
The new instance uses a privileged port. Refer to the privileged port configuration information in the product documentation.

Category:
Configuration

Cause:

Action:

OHS-04516
Instance name "{0}" is not valid.

Category:
Configuration

Cause:

Action:

OHS-04517
Instance names are limited to thirty characters, must begin with a letter, may contain letters, numbers, -, or _, and must not be one of the following reserved names(ignoring letter case): {0}

Category:
Configuration

Cause:

Action:

OHS-04519
OHS instance "{0}" was successfully created.

Category:
Configuration

Cause:

Action:

OHS-04520
OHS instance "{0}" was successfully deleted.

Category:
Configuration

Cause:

Action:

OHS-04521
ohs_addAdminProperties() failed.

Category:
Configuration

Cause:

Action:

OHS-04522
ohs_addNMProperties() failed.

Category:
Configuration

Cause:

Action:

OHS-04523
ohs_createTestDomain() failed.

Category:
Configuration

Cause:

Action:

OHS-04524
Domain "{0}" already exists.

Category:
Configuration

Cause:

Action:

OHS-04525
Privileged ports are not supported with this command.

Category:
Configuration

Cause:

Action:

OHS-04526
NodeManager is unreachable. "{0}" might be in undeletable state because the NodeManager is unreachable.

Category:
Configuration

Cause:

Action:

OHS-04527
ohs_exportKeyStore() failed.

Category:
Configuration

Cause:

Action:

OHS-04528
Disconnect from WebLogic server before using this command.

Category:
Configuration

Cause:

Action:

OHS-04529
Update of OHS instances failed.

Category:
Configuration

Cause:

Action:

OHS-04530
OHS instances have been updated successfully.

Category:
Configuration

Cause:

Action:

OHS-04532
This method is deprecated, please refer to product documentation for more details.

Category:
Configuration

Cause:

Action:

OHS-04533
Keystore "{0}" successfully exported to OHS instance "{1}".

Category:
Configuration

Cause:

Action:

24
OJRF-00001 to OJRF-00008

OJRF-00001
NOT on WLS - could not calculate application name for Jersey Client. Using default

Category:
JAXRS_CLIENT

Cause:

Action:

OJRF-00001
{0}

Category:
JAXRS_SERVER

Cause:

Action:

OJRF-00002
Could not retrieve ServerPlatformSupport: {0}

Category:
JAXRS_CLIENT

Cause:

Action:

OJRF-00002
State sensor for {0} couldn't be created. StateFactory didn't return valid sensor.

Category:
JAXRS_SERVER

Cause:

Action:

OJRF-00003
State sensor for {0} couldn't be created. Couldn't retrieve StateFactory.

Category:
JAXRS_SERVER

Cause:

Action:

OJRF-00004
Event sensor for {0} couldn't be created. EventFactory didn't return valid sensor.

Category:
JAXRS_SERVER

Cause:

Action:

OJRF-00005
Event sensor for {0} couldn't be created. Couldn't retrieve EventFactory.

Category:
JAXRS_SERVER

Cause:

Action:

OJRF-00006
Phase event sensor for {0} couldn't be created. PhaseEventFactory didn't return valid sensor.

Category:
JAXRS_SERVER

Cause:

Action:

OJRF-00007
Phase event sensor for {0} couldn't be created. Couldn't retrieve PhaseEventFactory.

Category:
JAXRS_SERVER

Cause:

Action:

OJRF-00008
OWSM ResourcePattern not available for application {0} and module {1}

Category:
JAXRS_SERVER

Cause:

Action:

25
OWS-00016 to OWS-60003

OWS-00016
no method to retrieve the daylight savings offset (getDSTSavings) defined on TimeZone

Category:
WebService

Cause:
Oracle did not find a method for setting daylight savings time for the default timezone on this system.

Action:
Check that default timezone is set correctly. Check that the Java Runtime Environment(TM) (JRE) that is used is complete.

OWS-00017
literal ArraySerializer.initialize error encountered: Exception message is {0} Stack trace is {1}

Category:
WebService

Cause:
Could not initialize Literal Array Serializer for JAXRPC databinding

Action:
System Internal Error - Contact Oracle Support Services

OWS-00018
getElementDateValue exception {0}

Category:
WebService

Cause:

Action:

OWS-00019
DOM Exception from removeElement {0}

Category:
WebService

Cause:

Action:

OWS-00020
problem found in XML parsing: {0}

Category:
WebService

Cause:

Action:

OWS-00021
Error creating XML mapping factory: {0}.

Category:
WebService

Cause:

Action:

OWS-00022
The WSDL generator can process only one service at a time. The first service is used.

Category:
WebService

Cause:

Action:

OWS-00023
could not copy {0} to {1}

Category:
WebService

Cause:

Action:

OWS-00024
{0} Failed to load dependent class: {1}

Category:
WebService

Cause:

Action:

OWS-00025
Exception converting WSDL types to XML Schema: {0}

Category:
WebService

Cause:

Action:

OWS-00028
Warning while processing WSM client configuration: {0}.

Category:
WebService

Cause:

Action:

OWS-00029
Error reading WSM client configuration file: {0}.

Category:
WebService

Cause:
The client side proprietry descriptor is invalid

Action:
Validate the client properietary descriprtor as per the schema "http://xmlns.oracle.com/oracleas/schema/11/oracle-webservices-client-11_1.xsd"

OWS-00030
Failed to find wsm client configuration file {0}

Category:
WebService

Cause:
The user specified client side oracle webservices proprietary configuration file is missing.

Action:
Ensure the valid location of client side config file is provided or it's available in classpath

OWS-00031
Warning while processing WSM server configuration: {0}.

Category:
WebService

Cause:

Action:

OWS-00032
Error reading WSM server configuration file: {0}.

Category:
WebService

Cause:
Cannot read WSM server configuration file

Action:
Ensure given WSM configuration file(Oracle proprietry descriptor) at server side is valid

OWS-00033
Failed to find deployment descriptor file {0}

Category:
WebService

Cause:
Could not find deployment descriptor file

Action:
Ensure server side deployment descriptor file is not missing

OWS-00034
<input> element of operation "{0}" in binding "{1}" does not define name attribute. The default name "{2}" does not match the name defined in the corresponding portType section: "{3}". Add name attribute in the <input> element using same value in portType to achieve interoperability.

Category:
WebService

Cause:

Action:

OWS-00035
<output> element of operation "{0}" in binding "{1}" does not define name attribute. The default name "{2}" does not match the name defined in the corresponding portType section: "{3}" Add name attribute in the <output> element using same value in PortType to achieve interoperability.

Category:
WebService

Cause:

Action:

OWS-00036
XML fragment top level tag name "{0}" has been corrected to "{1}"

Category:
WebService

Cause:

Action:

OWS-00037
No method found in SEI: {0}

Category:
WebService

Cause:

Action:

OWS-00038
A WSDL port in the model is missing a name

Category:
WebService

Cause:

Action:

OWS-00039
The schema using the namespace of {0} may cause unexpected failures, use {1} instead.

Category:
WebService

Cause:

Action:

OWS-00040
The element {0} in the supplied deployment descriptor will be ignored.

Category:
WebService

Cause:

Action:

OWS-00043
The WSDL contains a mixture of document and rpc styles, the generated WSDL will need to be modified to work correctly.

Category:
WebService

Cause:

Action:

OWS-00044
There is no management configuration for service: {0} in supplied proprietary deployment descriptor {1}, make sure the service name is correct

Category:
WebService

Cause:

Action:

OWS-00045
{0} does not have all the getter and setter methods. Set overwriteBeans to true to allow re-generation of correct value type class.

Category:
WebService

Cause:

Action:

OWS-00046
Cannot update web.xml file, <url-pattern> {0} already exists.

Category:
WebService

Cause:
The file output/war/WEB-INF/web.xml already contains a URL pattern that the system wants to use for another servlet mapping.

Action:
Specify a unique uri argument or change the url-pattern in the existing web.xml.

OWS-00047
Could not update web.xml because <servlet-name> "{0}" already exists. The value of <servlet-name> generated by Web Services Assembler is the port name. If bottom-up assembly is used, specify a portName argument value that does not already exist. If topdown assembly or the genDDs command is used, put the two Web services in different WAR files, so that they do not share deployment descriptors.

Category:
WebService

Cause:
The file output/war/WEB-INF/web.xml contained the URL and it was assigned to another servlet.

Action:
For bottom-up assembly specify a different portName. For top-down assembly or genDDs separate two Web services into different WAR files or change the name of the servlet in the web.xml file.

OWS-00048
Could not update webservices.xml because <webservice-description-name> "{0}" already exists. The value of the <webservice-description-name> generated by Web Services Assembler is always the service name. If bottom-up assembly is used, specify a serviceName argument value that does not already exist. If topdown assembly or the genDDs command is used, put the two Web services in different WAR files so they do not share deployment descriptors.

Category:
WebService

Cause:
The file output/war/WEB-INF/webservices.xml already contains a webservice-description-name. The system wants to re-use this name for a new Web service. The value of the <webservice-description-name> generated by the system is always the service name.

Action:
If bottom-up assembly is used, specify a serviceName argument value that does not already exist. If top-down assembly or the genDDs command is used, put the two Web services in different WAR files, so that they do not share deployment descriptors.

OWS-00049
Could not update webservices.xml because <port-component-name> "{0}" already exists. The value of <port-component-name> generated by Web Services Assembler is always the port name. If bottom-up assembly is used, specify a portName argument value that does not

already exist. If topdown assembly or the genDDs command is used, put the two Web services in different WAR files, so they do not share deployment descriptors.

Category:
WebService

Cause:
The file output/war/WEB-INF/webservices.xml already contains a port-component-name that the system wants to use for a new port. The value of the <port-component-name> generated by the system is always the port name.

Action:
If bottom-up assembly is used, specify a portName argument value that does not already exist. If top-down assembly or the genDDs command is used, put the two Web services in different WAR files, so that they do not share deployment descriptors.

OWS-00050
Could not update oracle-webservices.xml because <webservice-description> name "{0}" already exists.The name of the <webservice-description> generated by Web Services Assembler is always the service name. If bottom-up assembly is used, specify a serviceName argument value that does not already exist. If topdown assembly or the genDDs command is used, put the two Web services in different WAR files, so they do not share deployment descriptors.

Category:
WebService

Cause:
The file output/war/WEB-INF/oracle-webservices.xml already contains a webservice-description-name that the system wants to use for a new webservice. The value of the <webservice-description-name> generated by the system is always the service name.

Action:
If bottom-up assembly is used, specify a serviceName argument value that does not already exist. If top-down assembly or the genDDs command is used, put the two Web services in different WAR files so they do not share deployment descriptors.

OWS-00051
Could not update oracle-webservices.xml because <port-component> name "{0}" already exists. The value of <port-component> name generated by Web Services Assembler is always the port name. If bottom-up assembly is used, specify a portName argument value that does not already exist. If topdown assembly or the genDDs command is used, put the two Web services in different WAR files so they do not share deployment descriptors.

Category:
WebService

Cause:
The file output/war/WEB-INF/webservices.xml already contains a port-component name that the system wants to use for a new port. The value of the <port-component> name generated by the system is always the port name.

Action:
If bottom-up assembly is used, specify a portName argument value that does not already exist. If top-down assembly or the genDDs command is used, put the two Web services in different WAR files so they do not share deployment descriptors.

OWS-00052
Could not update oracle-webservices.xml because <endpoint-address-uri> "{0}" already exists. Specify a uri argument value that does not already exist.

Category:
WebService

Cause:
The file output/war/WEB-INF/oracle-webservices.xml already contains an endpoint-address-uri that the system wants to use for a new webservice port.

Action:
Specify a uri argument value that does not already exist.

OWS-00053
The wire signature of operation by name "{0}" is same as operation by name "{1}". This does not conform to WS-I Basic Profile v1.1. R2710: The operations in a wsdl:binding in a description MUST result in wire signatures that are different from one another. An endpoint that supports multiple operations must unambiguously identify the operation being invoked based on the input message that it receives. This is only possible if all the operations specified in the wsdl:binding associated with an endpoint have a unique wire signature.

Category:
WebService

Cause:

Action:

OWS-00054
When "linkReceiveWithReplyTo" is true, either receive destination/connection-factory or reply-to destination/connection-factory must be set.

Category:
WebService

Cause:
The linkReceiveWithReplyTo argument requires the receive or reply-to arguments defined so the system can make the values the same.

Action:
Specify replyToConnectionFactoryLocation and (replyToQueueLocation or replyToTopicLocation) or specify receiveConnectionFactoryLocation and (receiveQueueLocation or receiveTopicLocation).

OWS-00055
When "linkReceiveWithReplyTo" is true, the value of parameter "{0}" and parameter "{1}" should be same.

Category:
WebService

Cause:
When the argument linkReceiveWithReplyTo is set to true and both replyTo* and receive* arguments are specified they must have the same value.

Action:
Either remove one of the arguments shown in the message or set the arguments to the same value.

OWS-00056
JMS delivery mode "{0}" is invalid, ignore this setting.

Category:
WebService

Cause:

Action:

OWS-00057
The received SOAP fault contains non standard fault element: "{0}". This element will be ignored.

Category:
WebService

Cause:

Action:

OWS-00058
The class "{0}" exists, but could not be loaded.

Category:
WebService

Cause:

Action:

OWS-00059
Ignoring method "{1}" in SEI "{0}" because it is not JAX-RPC compliant. The reason is "{2}"

Category:
WebService

Cause:

Action:

OWS-00060
Ignoring property name "{0}" in Java exception "{1}" because it is not JAX-RPC compliant

Category:
WebService

Cause:

Action:

OWS-00061
Ignoring property name "{0}" in Java class "{1}" because it is not JAX-RPC compliant

Category:
WebService

Cause:

Action:

OWS-00062
Ignoring exception of type "{0}" in Java method "{1}" because it is not JAX-RPC compliant

Category:
WebService

Cause:

Action:

OWS-00064
Attribute "schemaLocation" is not present on a schema import element.

Category:
WebService

Cause:

Action:

OWS-00065
Interface "{0}" is not JAX-RPC compliant: it does not extend java.rmi.Remote.

Category:
WebService

Cause:

Action:

OWS-00066
Method "{0}" is not JAX-RPC compliant: it does not throw java.rmi.RemoteException.

Category:
WebService

Cause:

Action:

OWS-00067
There is no management configuration for port {0} in the supplied proprietary deployment descriptor. Ensure the port name is correct.

Category:
WebService

Cause:

Action:

OWS-00070
No matching type found for the custom type mapping with QName {0}

Category:
WebService

Cause:
A custom type has been defined in an oracle-webservices.xml file but no associated type can be found in the schemas associated with the webservice.

Action:
Remove the custom type mapping or correct the name of the custom type mapping so it matches a type in the schema.

OWS-00071
Custom type mappings for global elements are not supported. The custom type mapping with the QName of {0} will not be applied to the global element.

Category:
WebService

Cause:

Action:

OWS-00073
A failure occurred during Oracle Web Services Management agent interceptor {0} processing. {1}

Category:
WebService

Cause:
Could not process Oracle Web Services Management Agent interceptor

Action:
System Internal Error - Contact Oracle Support Services

OWS-00074
{0} does not have all the getter and setter methods. Ensure the user defined class matches type {1}.

Category:
WebService

Cause:

Action:

OWS-00075
Schema with schema namespace {0} is not supported

Category:
WebService

Cause:

Action:

OWS-00076
The service implementation class: {0} does not implement java.io.Serializable. This class is not suitable for clustered environments indicated by the argument recoverable=true.

Category:
WebService

Cause:

Action:

OWS-00077
The Value Type class: {0} does not have a valid Java Bean pattern.

Category:
WebService

Cause:

Action:

OWS-00084
Failed to find Oracle Web Services Management agent configuration {0}

Category:
WebService

Cause:
Could not find Oracle Web Services Management agent configuration file

Action:
Ensure correct location of OWSM agent configuration file is provided

OWS-00085
The schema element {0} is not supported. The type {1} uses this schema element and will be ignored.

Category:
WebService

Cause:

Action:

OWS-00086
The nested generic type {0} is not supported.

Category:
WebService

Cause:

Action:

OWS-00101
Mapped {0} to javax.xml.soap.SOAPElement.

Category:
WebService

Cause:
The system defaults to a SOAP element, since it could not determine how to map the specified schema type to a Java Bean.

Action:
Switching to a different data binding like JAXB may allow the system to create Java objects for the type.

OWS-00102
Mapped {0} to javax.xml.soap.SOAPElement{2}. Reason for not creating a custom Java type: {1}

Category:
WebService

Cause:

Action:

OWS-00103
nested model group is not supported.

Category:
WebService

Cause:

Action:

OWS-00104
namespace name constraint is not supported (except for ##any, ##other).

Category:
WebService

Cause:

Action:

OWS-00105
choice is not supported.

Category:
WebService

Cause:

Action:

OWS-00106
wildcard or element is not supported.

Category:
WebService

Cause:

Action:

OWS-00107
multiple occurrences are not supported.

Category:
WebService

Cause:

Action:

OWS-00108
simple or mixed content is not supported.

Category:
WebService

Cause:

Action:

OWS-00109
a mismatch was detected in the parent type.

Category:
WebService

Cause:

Action:

OWS-00110
an unsupported simple type.

Category:
WebService

Cause:

Action:

OWS-00111
expected a soap-enc type.

Category:
WebService

Cause:

Action:

OWS-00112
found a simple type with attributes.

Category:
WebService

Cause:

Action:

OWS-00113
mixed content was seen, this may not be a valid SOAP type.

Category:
WebService

Cause:

Action:

OWS-00114
use of an unimplemented feature.

Category:
WebService

Cause:
An unimplemented feature is used in the schema.

Action:
Avoid the unimplemented feature or use the SAAJ API to construct the XML element.

OWS-00115
the base type is not supported.

Category:
WebService

Cause:
An unimplemented feature is used in the base type definition.

Action:
Avoid the unimplemented feature or use the SAAJ API to construct the XML element.

OWS-00119
Deleting field: "{0}"

Category:
WebService

Cause:

Action:

OWS-00126
Deleting unused method: "{0}"

Category:
WebService

Cause:

Action:

OWS-00129
Changing parameter type of "{0}" from "{1}" to "{2}"

Category:
WebService

Cause:

Action:

OWS-00130
Adding new parameter "{0}"

Category:
WebService

Cause:

Action:

OWS-00131
Deleting old parameter "{0}"

Category:
WebService

Cause:

Action:

OWS-00132
Changing return type of "{0}" from "{1}" to "{2}"

Category:
WebService

Cause:

Action:

OWS-00136
Adding initializer "{0}" to field "{1}"

Category:
WebService

Cause:

Action:

OWS-00137
Removing initializer "{0}" from field "{1}"

Category:
WebService

Cause:

Action:

OWS-00138
Changing initializer of field "{0}" from "{1}" to "{2}"

Category:
WebService

Cause:

Action:

OWS-00139
The body of the method by name "{0}" could not be merged. The new method required code is "{1}"

Category:
WebService

Cause:
During top-down generation JDeveloper could not merge the generated code and modified code.

Action:
None

OWS-00140
No body expected for the method "{0}".

Category:
WebService

Cause:
During top-down generation JDeveloper found unexpected code in the Java source file provided by the user.

Action:
None

OWS-00141
HTTP transport error: {0}

Category:
WebService

Cause:
Error while getting the SOAPConnectionFactory object due to unsupported SAAJ communication infrastructure

Action:
System Internal Error - Contact Oracle Support Services

OWS-00142
local transport error: {0}

Category:
WebService

Cause:
Error occcured while processing request

Action:
System Internal Error - Contact Oracle Support Services

OWS-00143
service error: {0}

Category:
WebService

Cause:
Service Invocation failed. It might be because of an error while generating the stub implementation class or a dynamic proxy.

Action:
None

OWS-00144
not an interface: {0}

Category:
WebService

Cause:
In the createService(Class serviceInterface, QName name) method client code has provided an interface that is not a Service interface.

Action:
Ensure that the supplied interface extends javax.xml.rpc.Service

OWS-00145
cannot locate service implementation class for service: {0}

Category:
WebService

Cause:
An error occurred while generating a stub implementation class or a dynamic proxy. The service implementation class could not be found in the classpath.

Action:
Ensure that the service implementation class is available in the classpath.

OWS-00146
failed to create service implementation instance: {0}

Category:
WebService

Cause:
An error occurred while generating a stub implementation class or a dynamic proxy. The service implementation class does not implement a conctere service interface and thus could not be instantiated.

Action:
Ensure that specified service implementation class implements JAXRPC service interface and it's available in the classpath.

OWS-00147
dynamic invocation error: {0}

Category:
WebService

Cause:
Unexpected Error while invoking the service method.

Action:
Ensure that the DII client that invoking the serivce is configured correctly.

OWS-00148
service: {0} does not contain port: {1}

Category:
WebService

Cause:
Service Invocation failed because the <wsdl:service> element does not contain any ports.

Action:
Ensure that the <wsdl:service> element has atleast one port defined.

OWS-00149
port: {0} does not contain operation: {1}

Category:
WebService

Cause:
Service Invocation failed because service endpoint does not contain specified operation.

Action:
Ensure that DII client invoking the operation that advertised in the service descriptor i.e WSDL.

OWS-00150
property: "{0}" must be set on a Call object before it can be invoked in this configuration

Category:
WebService

Cause:
The Dynamic Invocation Interface (DII) client has not set the required property on the Call object.

Action:
For DII client, ensure that all required properties are set correctly on Call object before invoking service.

OWS-00156
call object cannot be created without a TypeRegistry

Category:
WebService

Cause:
Service Invocation failed because the InternalTypeMappingRegistry for serialization/deserialization provided to the Call object is null

Action:
System Internal Error - Contact Oracle Support Services

OWS-00157
cannot set unrecognized property: {0} on a Call object

Category:
WebService

Cause:
Client code is trying to set a property that is not specified for Call objects.

Action:
Check the name of the property that is being set. Use only properties specified for Call objects.

OWS-00158
cannot get unrecognized property: {0} on a Call object

Category:
WebService

Cause:
Client code is trying to get a property that is not specified for Call objects.

Action:
Check the name of the property that client side code is trying to access. Use only properties specified for Call objects.

OWS-00159
WSDL data missing, this operation is not available

Category:
WebService

Cause:
An unconfigured Dynamic Invocation Interface (DII) client is using the getCalls(Qname portName) method on a Service object that does not have an associated WSDL.

Action:
Either use a fully configured DII client, or use a createCall() method that explicitly specifies all required port and operation information to create a Call object instance.

OWS-00160
WSDL data missing, {0}

Category:
WebService

Cause:
An unconfigured (Dynamic Invocation Interface (DII) client uses getPort method on Service Implementation object which is not supported when WSDL information is missing

Action:
Use the configured DII client by getting the service implementation object using creteService(java.net.URL wsdlDocLoc, QName name) method on ServiceFactory object

OWS-00161
output parameters are only available after invoke() has been called

Category:
WebService

Cause:
Dynamic Invocation Interface (DII) client code is trying to get the output parameters before invoking the service

Action:
Ensure that the client code has invoked the service first before accessing the value of output parameters.

OWS-00162
cannot set parameter or return types on this Call object

Category:
WebService

Cause:
Dynamic Invocation Interface (DII) client attempted to set parameter or return types on a Call object when service operation does not require input parameter and does not return anything.

Action:
Check whether Call obect requires to set parameter or return type by calling isParameterAndReturnSpecRequired() on Call object

OWS-00163
operation style: "{0}" not supported

Category:
WebService

Cause:
Dynamic Invocation Interface (DII) Client sets the Call.OPERATION_STYLE_PROPERTY to other than 'rpc' or 'document'

Action:
Set Call.OPERATION_STYLE_PROPERTY to either 'rpc' or 'document'

OWS-00164
encoding style: "{0}" not supported

Category:
WebService

Cause:
Dynamic Invocation Interface (DII) client sets the ENCODINGSTYLE_URI_PROPERTY to an unsupported value i.e other than 'http://schemas.xmlsoap.org/soap/encoding' or null

Action:
Use either 'encoded' or 'literal' encoding style.

OWS-00165
could not find service: {0} in the specified WSDL file. The service names found were: {1}

Category:
WebService

Cause:
Service name provided by client code is not available in the specified WSDL.

Action:
Check the Service name used by the client code and ensure that correct Service name is used as per the specified WSDL.

OWS-00166
could not dispatch to method: {0} known methods are: {1}

Category:
WebService

Cause:
Operation that Dynamic Invocation Interface (DII) client code is trying to invoke does not not match with any operation provided by the service.

Action:
Make sure correct Operation name is used by the DII client code while configuring Call Object.

OWS-00167
The attachment DataHandler object cannot be null

Category:
WebService

Cause:
The attachment DataHandler object cannot be null

Action:
Make sure DataHandler attached to Call object is not null

OWS-00168
error.build.wsdl.model: {0}

Category:
WebService

Cause:
Error in the WSDL Model generation at the client side during service invocation. The useWSI property was set to true, but the WSDL does not conform to the WSI basic profile.

Action:
Ensure that the specified WSDL is compliant to Web Services Interoperability(WS-I) Basic Profile.

OWS-00169
Wrong value type {0} for property {1}. java.io.File or org.w3c.dom.Element is expected

Category:
WebService

Cause:
An unexpected value was set on a Call object. The value must be either of type java.io.File or of type org.w3c.dom.Element.

Action:
Check the type of the value being set on the Call object.

OWS-00170
serialization error: {0}

Category:
WebService

Cause:
Serializer class is missing.

Action:
Make sure the serializer class is defined and available from the classpath.

OWS-00171
deserialization error: {0}

Category:
WebService

Cause:
Deserializer failed.

Action:
Check the incoming message.

OWS-00172
encoding error: {0}

Category:
WebService

Cause:
Failed to initialize dynamic serializer/deserializer for RPC/ENC request

Action:
System Internal Error - Contact Oracle Support Services

OWS-00173
malformed array type: {0}

Category:
WebService

Cause:
The arrayType attribute is missing. The array index is less than 0 or the end index is less than the start index.

Action:
Check the incoming message. Check the incoming message.

OWS-00174
serialized array has too many elements

Category:
WebService

Cause:
At least one array element position is outside the array boundaries in the inbound message.

Action:
Check the incoming message

OWS-00175
illegal array element position: {0}

Category:
WebService

Cause:
Either the array dimension is empty and the element position is not one, or the array dimension length is not equal to the element position length.

Action:
Check the incoming message

OWS-00176
missing array position attribute

Category:
WebService

Cause:
Sparse array does not have a position attribute

Action:
Check the incoming message

OWS-00177
array element position is out of bounds: {0}

Category:
WebService

Cause:
An array position value is outside the array bounds

Action:
Check the incoming message

OWS-00178
unexpected null value during serialization or deserialization

Category:
WebService

Cause:
Serializer cannot serialize a null object for a non-nillable parameter.Deserializer cannot deserialize null to a non-nillable object.

Action:
Make sure the parameter is not null. Check the incoming message.

OWS-00179
Unexpected error while processing a SOAP Message during {0}, message={1}

Category:
WebService

Cause:

Action:

OWS-00180
unexpected reference element during deserialization; the element "{0}" is not defined as a referenceable type

Category:
WebService

Cause:
Failed to deserialize the request message. The request element uses a reference type which is not specified in the WSDL.

Action:
Correct the WSDL definition or correct the request message.

OWS-00181
unexpected element type: expected={0}, actual={1}

Category:
WebService

Cause:
Failed to deserialize the request message. The request element type does not match what is defined in the WSDL.

Action:
Correct the WSDL definition or correct the request message.

OWS-00182
unexpected element name: expected={0}, actual={1}

Category:
WebService

Cause:
Failed to deserialize the request message. The request element name does not match what is defined in the WSDL.

Action:
Correct the WSDL definition or correct the request message.

OWS-00183
unexpected array element type: expected={0}, actual={1}

Category:
WebService

Cause:
The type of an array element does not match its definition in the schema.

Action:
Verify that the type of the array element being sent matches the type defined in the schema.

OWS-00184
non-local reference (href): {0}

Category:
WebService

Cause:
The href attribute, used to reference an attachment, is not specified using the "cid" (Content-ID) protocol string.

Action:
Change the value of the href attribute, used to reference an attachment, to a string that begins with "cid:".

OWS-00185
trailing block elements must have an id attribute

Category:
WebService

Cause:
An element in the SOAP message contains a reference to another element. However no element was found with an id attribute matching the reference.

Action:
Validate the correctness of the received message.

OWS-00186
malformed array dimensions: {0}

Category:
WebService

Cause:
The dimensions of the array specified in the SOAP message cannot be translated into a valid number. The bounds of the array are invalid. For example the lower bound of the array is larger than the upper bound.

Action:
Verify that the SOAP-ENC:arrayType attribute (for SOAP 1.1) or the arraySize attribute (for SOAP 1.2) is valid.

OWS-00187
multi-dimensional array is not regular

Category:
WebService

Cause:
One level in a multi-dimensional array instance is null or contains an invalid size.

Action:
Ensure that all levels of the multi-dimensional array conatin valid values.

OWS-00188
illegal array offset: {0}

Category:
WebService

Cause:
The value specified in the "offset" attribute of an array element is invalid.

Action:
Ensure that the value specified in the offset attribute of the array element in the SOAP message is within the range of the array dimensions.

OWS-00189
array has unexpected rank: expected={0}, actual={1}, arrayType={2}

Category:
WebService

Cause:
The rank of an array does not match the rank specified in the schema.

Action:
Verify that that the soapenc:rank attribute of the array element in the schema matches with the actual dimensions of the array in the SOAPMessage.

OWS-00190
array has unexpected dimensions: expected={0}, actual={1}, arrayType={2}

Category:
WebService

Cause:
The dimensions of an array in the SOAP element do not match those of the element defined in the Schema.

Action:
Verify that the SOAP message matches the WSDL definition

OWS-00191
unexpected encoding style: expected={0}, actual={1}

Category:
WebService

Cause:
The encoding style being used in the message is invalid for the SOAP version. For example, SOAP 1.1 expects the encoding style http://schemas.xmlsoap.org/soap/encoding/ while SOAP 1.2 expects a range of values, one of which is http://www.w3.org/2003/05/soap-encoding.

Action:
Ensure that the encoding style uri of the SOAP message is valid for the version of SOAP in use. Check the SOAP 1.1 and SOAP 1.2 for acceptable values.

OWS-00192
cannot encode XML type because it was not specified

Category:
WebService

Cause:
Unable to find XML type for object.

Action:
System Internal Error - Contact Oracle Support Services

OWS-00193
member {0} has already been defined

Category:
WebService

Cause:
While deserializing the SOAP message a duplicate member variable or setter/getter was found in the target object.

Action:
System Internal Error - Contact Oracle Support Services

OWS-00194
incomplete object encountered while deserializing

Category:
WebService

Cause:
Failure during deserialization (XML to Java).

Action:
System Internal Error - Contact Oracle Support Services

OWS-00195
circular reference detected while serializing: {0}

Category:
WebService

Cause:
An object is referenced from another object that it references. For example A->B->A. This circular reference is not supported in RPC-Literal or Doc-Literal web services.

Action:
Remove the circular dependency or change the web service to RPC-Encoded.

OWS-00196
no attachment with cid (Content-ID) "{0}" found in message

Category:
WebService

Cause:
The cid (Content-ID) for a particular attachment that was referenced from the SOAP body was not found.

Action:
Make sure that the cid is formatted properly. Examine the cid in the soap body with the Content-Id header of the SOAP Message MIME attachment and verify that they match.

OWS-00197
multiple attachments with the same cid (Content-ID) "{0}" found in message

Category:
WebService

Cause:
Found multiple attachments with the same cid (Content-ID). This field must be unique

Action:
If the SOAP message was manually constructed, verify that all the Content-ID headers contain a unique value.

OWS-00198
missing cid (Content-ID header) for attachment

Category:
WebService

Cause:
An attachment was missing the Content-Id header.

Action:
Examine the SOAP message and verify that all Content-Id headers contain a value.

OWS-00199
non "cid:" (Content-ID) reference: {0}

Category:
WebService

Cause:
A SwaRef attachment was found with an invalid reference to a MIME attachment. MIME attachment references must begin with the string "cid:".

Action:
Verify that the attachment reference begins with "cid".

OWS-00203
serializeAsAttachment specified but no AttachmentEncoder was provided for type: "{0}"

Category:
WebService

Cause:
Missing serializer for a particular attachment type.

Action:
System Internal Error - Contact Oracle Support Services

OWS-00204
a deserializer must be registered with a deserialization state before it will accept listeners

Category:
WebService

Cause:
A serializer class was not found during initialization of the serializer framework.

Action:
System Internal Error - Contact Oracle Support Services

OWS-00205
cannot decode XML type "{0}"

Category:
WebService

Cause:
Unable to construct an object from an XML instance (element).

Action:
System Internal Error - Contact Oracle Support Services

OWS-00206
cannot serialize type "{0}"

Category:
WebService

Cause:
An appropriate default serializer for the specified type could not be found.

Action:
A custom serializer must be used for the indicated type. Implementing a custom serializer for a Web service is described in the Oracle Application Server Web Services Developer's Guide.

OWS-00207
null soap version not allowed.

Category:
WebService

Cause:
The SOAP message did not contain enough information to determine the version of the SOAP specification used.

Action:
Typcially the SOAP version is determined by inspecting the namespace declared on the root element (Envelope) of the SOAP message. This value should be one of http://schemas.xmlsoap.org/soap/envelope/ for SOAP 1.1 or http://www.w3.org/2003/05/soap-envelope for SOAP 1.2.

OWS-00208
cannot have enc:id and enc:ref attributes on the same element.

Category:
WebService

Cause:
The SOAP message element contains both an id and a ref attribute. Using both on the same element is illegal.

Action:
The Webservice client that created the message must be modified so that invalid SOAP messages are not created.

OWS-00209
unexpected element name: expected={0}, actual={1}

Category:
WebService

Cause:
The deserializer encountered an unexpected element name when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that the SOAP messages it creates conform to the messages described in this Webservice's WSDL.

OWS-00210
unexpected element type: expected={0}, actual={1}

Category:
WebService

Cause:
The deserializer encountered an unexpected element type when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that the SOAP messages it creates conform to the messages described in this Webservice's WSDL.

OWS-00211
unexpected null

Category:
WebService

Cause:
The (de)serializer encountered an unexpected null element/object when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that the SOAP messages it creates conform to the messages described in this Webservice's WSDL.

OWS-00212
unknown prefix in QName literal: {0}

Category:
WebService

Cause:
The deserializer cannot figure out the Namespace URI for the given prefix when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that invalid SOAP messages are not created.

OWS-00213
invalid XSD date: {0}

Category:
WebService

Cause:
The deserializer encountered an invalid XSD date when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that SOAP messages with invalid XSD dates are not created.

OWS-00214
invalid XSD boolean value: {0}

Category:
WebService

Cause:
The deserializer encountered an invalid XSD boolean when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that SOAP messages with invalid XSD boolean are not created.

OWS-00215
attachment location not found on element

Category:
WebService

Cause:
The deserializer cannot determine the attachment location on an element with binary type.

Action:
The Webservice client that created the message must be modified so that SOAP messages with attachments will correctly reference the attachments.

OWS-00216
attachment with id {0} not found in message

Category:
WebService

Cause:
The deserializer cannot find the attachment from the specified location on an element with binary type.

Action:
The Webservice client that created the message must be modified so that SOAP messages with attachments will correctly reference the attachments.

OWS-00217
invalid XSD positiveInteger value: {0}

Category:
WebService

Cause:
The deserializer encountered an invalid XSD positiveInteger when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that SOAP messages with invalid XSD positiveInteger are not created.

OWS-00218
invalid XSD nonNegativeInteger value: {0}

Category:
WebService

Cause:
The deserializer encountered an invalid XSD nonNegativeInteger when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that SOAP messages with invalid XSD nonNegativeInteger are not created.

OWS-00219
invalid XSD negativeInteger value: {0}

Category:
WebService

Cause:
The deserializer encountered an invalid XSD negativeInteger when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that SOAP messages with invalid XSD negativeInteger are not created.

OWS-00220
invalid XSD nonPositiveInteger value: {0}

Category:
WebService

Cause:
The deserializer encountered an invalid XSD nonPositiveInteger when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that SOAP messages with invalid XSD nonPositiveInteger are not created.

OWS-00222
invalid XSD unsignedLong value: {0}

Category:
WebService

Cause:
The deserializer encountered an invalid XSD unsignedLong when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that SOAP messages with invalid XSD unsignedLong are not created.

OWS-00223
invalid XSD unsignedInt value: {0}

Category:
WebService

Cause:
The deserializer encountered an invalid XSD unsignedInt when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that SOAP messages with invalid XSD unsignedInt are not created.

OWS-00224
invalid XSD unsignedShort value: {0}

Category:
WebService

Cause:
The deserializer encountered an invalid XSD unsignedShort when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that SOAP messages with invalid XSD unsignedShort are not created.

OWS-00225
invalid XSD unsignedByte value: {0}

Category:
WebService

Cause:
The deserializer encountered an invalid XSD unsignedByte when processing the SOAP message.

Action:
The Webservice client that created the message must be modified so that SOAP messages with invalid XSD unsignedByte are not created.

OWS-00227
error in initialization of standard type mapping: {0}

Category:
WebService

Cause:
Internal error initializing the standard type mapping.

Action:
System Internal Error - Contact Oracle Support Services

OWS-00228
{0} : is not a supported (de)serialization mechanism

Category:
WebService

Cause:
The (de)serializer factory does not support the reported XML processing mechanism type.

Action:
System Internal Error - Contact Oracle Support Services

OWS-00229
type mapping registration failed: {0}

Category:
WebService

Cause:
An unexpected error occurred during registration of a Java to XML mapping. Check the nested error for the real cause.

Action:
Look at the nested error to determine what action to take.

OWS-00230
type mapping retrieval failed: {0}

Category:
WebService

Cause:
An unexpected error occurred during retrieval of a Java to XML mapping. Check the nested error for the real cause.

Action:
Look at the nested error to determine what action to take.

OWS-00231
type mapping does not support the specified encoding style: {0}

Category:
WebService

Cause:
The system does not support the specified schema type and encoding.

Action:
Change the encodingStyle defined in the SOAP binding in the WSDL to a supported value.

OWS-00232
there is no type mapping for the specified encoding style: {0}

Category:
WebService

Cause:
The system does not support the specified encoding.

Action:
Change the encodingStyle defined in the SOAP binding in the WSDL to a supported value.

OWS-00233
no serializer is registered for ({0}, {1})

Category:
WebService

Cause:
The system could not find a serializer that can convert the Java object to XML.

Action:
Create a custom type mapping and serializer that can covert the Java object to XML.

OWS-00234
no deserializer is registered for (java type: {0}, schema type: {1})

Category:
WebService

Cause:
The system could not find a deserializer that can convert the XML to a Java object.

Action:
Create a custom type mapping and serializer that can covert the XML to a Java object.

OWS-00235
no deserializer is registered for schema type: {0}

Category:
WebService

Cause:
The system could not find a deserializer that can convert the XML to a Java object.

Action:
Create a custom type mapping and serializer that can covert the XML to a Java object.

OWS-00236
no deserializer is registered for java type: {0}

Category:
WebService

Cause:
The system could not find a deserializer that can convert the XML to a Java object.

Action:
Create a custom type mapping and serializer that can covert the XML to a Java object.

OWS-00237
dynamic resolution failed to find a serializer for java type:{0}, xml type {1}

Category:
WebService

Cause:
An entry in a list or collection is a type that is not supported by the system.

Action:
Change the instance of the entry to a supported Java type.

OWS-00238
dynamic resolution failed to find a serializer for java type: {0}, xmlType: {1}

Category:
WebService

Cause:
An entry in a list or collection is a type that is not supported by the system.

Action:
Change the instance of the entry to a supported Java type.

OWS-00241
Map entry key cannot be of java type:"{0}", xml type "{1}"

Category:
WebService

Cause:
The key for a map entry has a type mapping for an object that the system does not support.

Action:
Change the signature of the Java class to a supported Java type or change the instance of the key to a supported type.

OWS-00242
Map entry value cannot be of Java type:"{0}", XML type was "{1}"

Category:
WebService

Cause:
The value for a map entry has a type mapping for an object that the system does not support.

Action:
Change the signature of the Java class to a supported Java type or change the instance of the value to a supported type.

OWS-00243
Item in array cannot be of java type:"{0}"

Category:
WebService

Cause:
An item in an array is a type that is not supported by the system.

Action:
Change the signature of the Java class to a supported Java type or change the instance of the value to a supported type.

OWS-00245
unexpected null value for literal data

Category:
WebService

Cause:
The element defined in the schema has a nillable attribute set to false but no value was found in the message.

Action:
Change the client to supply a value for the literal type, or change the schema to accept nillable types.

OWS-00246
unexpected element name: expected={0}, actual={1}

Category:
WebService

Cause:
A message contains an element that the system does not expect.

Action:
Change the client to send messages corresponding to the schema, or change the schema to correspond to the messages.

OWS-00247
expected element is missing: {0}

Category:
WebService

Cause:
The message does not contain an element that is defind as required in the schema.

Action:
Change the schema to make the element optional, or change the client so that the message will include the required element.

OWS-00248
expected simple content, found element name: {0}

Category:
WebService

Cause:
The system was expecting a simple content in the message but found an element instead.

Action:
Change the client to send messages corresponding to the schema, or change the schema to correspond to the messages.

OWS-00249
object not initialized before use

Category:
WebService

Cause:
A serializer was not initialized before calling a method that requires initialization.

Action:
System Internal Error - Contact Oracle Support Services

OWS-00250
{0} is not an array type

Category:
WebService

Cause:
The system found a Java object that is not an array when an array is expected.

Action:
System Internal Error - Contact Oracle Support Services

OWS-00251
expected {0} parameter(s) but received: {1}. Expected parameters: {3}, received parameters: {4}

Category:
WebService

Cause:
The number of parameters in the request SOAP message is incorrect.

Action:
Confirm that the client is based on the correct version of the WSDL definition.

OWS-00252
illegal deserialization state: no deserializer is available for the current element

Category:
WebService

Cause:
There is no deserializer registered for the element.

Action:
A custom serializer must be used for the indicated type. Implementing a custom serializer for a Web service is described in the Oracle Application Server Web Services Developer's Guide.

OWS-00253
Invalid base64 data

Category:
WebService

Cause:
The SOAP request content being processed by the XSDBase64BinaryEncoder is not Base64 encoded.

Action:
Confirm that the client is based on the correct, current version of the WSDL document.

OWS-00254
generator error: {0}

Category:
WebService

Cause:
An unexpected exception occurred during a generation operation.

Action:
Contact Oracle Support Services.

OWS-00255
can"t write file: {0}

Category:
WebService

Cause:
A generated file could not be written to disk. The most likely causes include insufficient disk space or permissions.

Action:
Free some disk space or ensure that the process in which the generator is invoked is run as a user with sufficient permissions.

OWS-00256
can"t create directory: {0}

Category:
WebService

Cause:
The directory for writing a generated file could not be created. The most likely causes include insufficient disk space or permissions.

Action:
Free some disk space or ensure that the process in which the generator is invoked is run as a user with sufficient permissions.

OWS-00257
unsupported type encountered: '{'{1}'}'{0}

Category:
WebService

Cause:
Serialization is not supported for this XML type.

Action:
A custom serializer must be used for the indicated type. Implementing a custom serializer for a Web service is described in the Oracle Application Server Web Services Developer's Guide.

OWS-00258
no Java type for XML type: {0}

Category:
WebService

Cause:
Unable to determine the corresponding Java type for a structured XML type when generating a serializer.

Action:
Ensure that a Java type is associated with the structured XML type and that the custom serializer mapping is correct.

OWS-00259
unsupported encoding encountered: {0}

Category:
WebService

Cause:
The encoding URI of custom serializer mapping does not match that of either SOAP 1.1 or SOAP 1.2.

Action:
Correct the URI encoding of the custom serializer mapping.

OWS-00260
tie class generation error: {0}

Category:
WebService

Cause:
When generating the tie class for a document literal operation, either more than one non-embedded parameter was found, or there were both embedded and non-embedded parameter.

Action:
This sanity check should not have failed. Verify that the document literal operation is correct in the WSDL.

OWS-00262
There is no management configuration for port {0} in the supplied proprietary deployment descriptor. Ensure that the port name is correct

Category:
WebService

Cause:
There is no management configuration information for the port in the supplied management configuration file.

Action:
Verify that the port name is correct and the management configuration file is complete.

OWS-00263
Could not find the Java class {0} for constructor analysis.

Category:
WebService

Cause:
Could not find the Java class for constructor analysis when generating its serializer.

Action:
Check the Java class name and the classpath where the Java class is loaded.

OWS-00264
Current SOAP Version is null. Check port to make sure SOAP version is set.

Category:
WebService

Cause:
Could not determine the SOAP version when generating serializer.

Action:
Verify that the SOAP version is set in the WSDL.

OWS-00266
When using JMS transport, either all operations must be one-way, or the replyToConnectionFactoryLocation and replyToQueueLocation must be specified.

Category:
WebService

Cause:
When using JMS transport for any two-way operation, the replyToConnectionFactoryLocation and replyToQueueLocation parameters must be specified with the jsmAssemble command.

Action:
Re-run the jmsAssemble command with replyToConnectionFactoryLocation and replyToQueueLocation parameters.

OWS-00267
cannot dispatch operation with more that one body block: {0}

Category:
WebService

Cause:
Cannot generate tie class for operations with more than one body block.

Action:
Verify that the offending operation has no more than one body block.

OWS-00268
cannot dispatch operation - either operation names are non-unique, or SOAPAction strings are non-unique: {0}

Category:
WebService

Cause:
Cannot generate tie class for operation with non-unique operation name and non-unique SOAPAction.

Action:
Verify that both the operation name and SOAPAction are unique in the WSDL.

OWS-00269
no encoder for type "{0}" and Java type "{1}"

Category:
WebService

Cause:
Unable to find an encoder for a type and its corresponding Java type when generating serializer.

Action:
Check whether the type is valid and supported.

OWS-00270
Invalid type in xsd:list type "{0}" and Java type "{1}"

Category:
WebService

Cause:
Unable to find an encoder for the list item type and its corresponding Java type when generating serializer.

Action:
Check whether the list item XML type is valid and supported.

OWS-00271
handler error: {0}

Category:
WebService

Cause:
A handler error occurred, check the nested error for the real cause.

Action:
Look at the nested error to determine what action to take.

OWS-00272
A HandlerChain can only contain Handler instances: {0}

Category:
WebService

Cause:
A non-handler instance was found in the handler chain.

Action:
Remove the offending instance,

OWS-00274
cannot create XSLT transformer for the WSDL

Category:
WebService

Cause:
Failed to create a XSLT Transformer object for presentation of WSDL.

Action:
Check whether the web service endpoint is valid and the service is properly deployed.

OWS-00275
WSDL transformation failed

Category:
WebService

Cause:
XSLT Transformation failed when presenting WSDL.

Action:
Check whether the web service endpoint is valid and the service is properly deployed.

OWS-00276
model error: {0}

Category:
WebService

Cause:
A nested model or modeler exception occurred, most likely caused by an invalid WSDL.

Action:
Verify that the WSDL is a valid one.

OWS-00277
unsupported XML Schema feature ({0})

Category:
WebService

Cause:
An unsupported XML Schema feature was encountered during processing of WSDL schema.

Action:
Remove the unsupported XML Schema feature from WSDL schema.

OWS-00278
unsupported type ({0}): {2}:{1}

Category:
WebService

Cause:
An unsupported XML Schema type was encountered during processing of a WSDL schema element.

Action:
Remove the unsupported type or change it to an equivalent supported type.

OWS-00279
unsupported type ({0}): {1}, caused by: {3}

Category:
WebService

Cause:
An unsupported XML Schema type was encountered during processing of a WSDL schema element. Error details are provided.

Action:
Look at the error details for possible action to handle the unsupported type.

OWS-00280
unsupported anonymous type ({0}), caused by: {1}

Category:
WebService

Cause:
An unsupported XML Schema type was encountered during processing of an anonymous WSDL schema element. Error details are provided.

Action:
Look at the error details for possible action to handle the unsupported type.

OWS-00281
invalid literal "{0}" in enumeration "{1}" (namespace: {2})

Category:
WebService

Cause:
An invalid literal value of an enumeration was encountered when processing a WSDL schema.

Action:
Correct the offending literal value in the enumeration.

OWS-00282
uniqueness constraint violation: {0} "{1}" already exists.

Category:
WebService

Cause:
A component with the specified name occurs multiple times

Action:
Check the validity of the WSDL or Java code for duplicate elements

OWS-00283
The value type {0} can not be generated because two members result in the same name of {1}. A jaxrpc mapping file must be specified to resolve this naming conflict.

Category:
WebService

Cause:
There is a naming conflict - two members have the same name

Action:
Use a JAX-RPC mapping file.

OWS-00285
parent of type "{0}" already set to "{1}", new value = "{2}"

Category:
WebService

Cause:
The specified type is duplicated within more than one parent type.

Action:
Rewrite the type hierarchy, so that this type only occurs on one parent.

OWS-00286
parent of fault "{0}" already set to "{1}", new value = "{2}"

Category:
WebService

Cause:
The specified fault is duplicated as a sub-type of more than one parent.

Action:
Ensure that the fault only occurs within a single parent.

OWS-00287
LiteralArrayWrapper element member already set.

Category:
WebService

Cause:
This element cannot be modeled as a LiteralArrayWrapper because it has more than one member

Action:
None

OWS-00288
LiteralArrayWrapper cannot have a parent type

Category:
WebService

Cause:
This element cannot be modeled as a LiteralArrayWrapper because it has a parent type

Action:
None

OWS-00289
LiteralArrayWrapper cannot have subtypes

Category:
WebService

Cause:
This element cannot be modeled as a LiteralArrayWrapper because it has a subtype

Action:
None

OWS-00290
LiteralArrayWrapper cannot have a content member

Category:
WebService

Cause:
This element cannot be modeled as a LiteralArrayWrapper because it has a content member

Action:
None

OWS-00293
class {0} not found.

Category:
WebService

Cause:
The specified Java class could not be loaded.

Action:
The class must exist in the classpath when strictJAXRPCValidation is turned on.

OWS-00295
unexpected type: {0}

Category:
WebService

Cause:
An unexpected type was found during the processing of your action. In the case of top-down design the WSDL contains an unsupported or invalid type. In the case of bottom-up design, the particular class file is currently not supported.

Action:
Top-down design pattern: Correct any problems within the WSDL file. If the WSDL is valid, then it contains types that are currently not supported. Bottom-up design pattern: Correct any type issues within the Java class. Otherwise, the class contains types that are currently not supported. You may want to consider using a different type.

OWS-00296
The following type is invalid because it implements java.rmi.Remote: {0}

Category:
WebService

Cause:
The serializable implementation class inappropriately implements java.rmi.Remote. This is not supported.

Action:
Change the implementation class to not implement java.rmi.Remote.

OWS-00297
class {0} does not have a public accessible empty constructor

Category:
WebService

Cause:
The serializable implementation class does not provide a public accessible no-arg constructor.

Action:
Provide a public no-arg constructor or provide a custom seriallizer.

OWS-00299
class "{0}" cannot have a JavaBean property "{1}" and a public member of the same name.

Category:
WebService

Cause:
The implementation class cannot contain public members with the same name as JavaBean properties.

Action:
Consider making the public member private or protected or renaming the property or JavaBean property.

OWS-00300
nested inner classes are not supported: {0}

Category:
WebService

Cause:
The implementation class contains a nested inner class, which is not supported.

Action:
Consider refactoring the implementation class to remove the nested inner class. See the Oracle Application Server Web Services Developer's Guide.

OWS-00301
Duplicate type name "{0}" for Java type "{1}" found. To remove this error do not specify a single typeNamespace for all value types or specify a mapping file. This error could also be caused when a type name has been used more than once.

Category:
WebService

Cause:
The same type name has been used for multiple Java types. Probably related to inner classes. A possible explanation is the erroneous use of a given type name multiple times.

Action:
Use separate namespaces for the value types or use a mapping file. See the Oracle Application Server Web Services Developer's Guide.

OWS-00302
Type "{0}" is used as a "{1}" and a "{2}"

Category:
WebService

Cause:
The same RMI Modeler type instance is used for two different XML types.

Action:
Correct the XML type or the XML type hierarchy such that there is one Modeler per XML type, or have one type subclass the other type.

OWS-00303
Type "{0}" implements more than one interface: "{1}", "{2}" ...

Category:
WebService

Cause:
The implementation class may implement only a single interface (SEI).

Action:
Consider refactoring the implementation class to implement a single interface.

OWS-00304
Type {0} references an invalid type {1}, which is invalid for the following reason: {2}

Category:
WebService

Cause:
The indicated type has a reference to an invalid type.

Action:
Consider modifying the implementation class to not reference the inappropriate type.

OWS-00305
Ignoring target namespace for schema: "{0}", WSDL target namespace is used for the value types in the same package as Service Endpoint: "{1}"

Category:
WebService

Cause:
The schema namespace is ignored and the WSDL target namespace will be used instead. This is because the namespace of the schema is different from the target namespace of the WSDL and the value types are in the same package as the Service Endpoint Interface (SEI).

Action:

OWS-00306
The constructor for {0} has {1} arguments of type {2}; This ambiguity may result in unexpected behavior. Use a mapping file to guarantee correctness.

Category:
WebService

Cause:
Multiple arguments of the same type introduce ambiguity that is difficult to resolve. This may cause unexpected results.

Action:
Consider using a JAX-RPC mapping file to eliminate the ambiguity.

OWS-00307
Service-specific exception {0} is not allowed to extend {1}.

Category:
WebService

Cause:
Runtime exceptions other than SOAPFaultException are not allowed.

Action:
Consider changing the exception to not be a runtime exception or make it a SOAPFaultException.

OWS-00308
Service-specific exception {0} is not allowed to implement {1}.

Category:
WebService

Cause:
Service exceptions must not implement the java.rmi.Remote interface.

Action:
Consider changing the exception to not implement Remote.

OWS-00314
invalid operation: {0}

Category:
WebService

Cause:
Invalid WSDL operation due to incorrect parameter order.

Action:
Correct the parameter order of the specified operation.

OWS-00315
invalid state while modeling operation: {0}

Category:
WebService

Cause:
System Internal Error

Action:
Contact Oracle Support Services

OWS-00316
result is "inout" parameter in operation: {0}

Category:
WebService

Cause:
In/out parameters are not allowed.

Action:
Consider changing the implementation to return a value.

OWS-00317
"{0}" specified in the parameterOrder attribute of message "{1}" is not a valid part of the message.

Category:
WebService

Cause:
The specified parameter(s) in parameterOrder of portType operation is not a valid part of the message.

Action:
Verify and correct the part name parameter specified in the WSDL portType: ensure that the operation parameterOrder is properly associated and used in the input and output message.

OWS-00318
one or more part names were omitted in the parameterOrder attribute of operation "{0}"

Category:
WebService

Cause:
A message part name was not specified in the WSDL portType operation parameterOrder.

Action:
Verify that input and output message part name are properly specified in the WSDL portType operation parameterOrder.

OWS-00319
parameter "{0}" of operation "{1}" appears with different types in the input and output messages

Category:
WebService

Cause:
The parameter used in an operation appears with different types in the input and output message.

Action:
Verify the type of the input and output message specified in the WSDL portType operation.

OWS-00320
missing header message definition for "{1}", referenced by the binding operation "{0}"

Category:
WebService

Cause:
The soap header message defined in the binding operation is not specified in the WSDL message definition.

Action:
Verify the soap header message defined in the binding operation. Ensure that it is properly specified in the WSDL message definition.

OWS-00321
missing operation "{0}" in port type, referenced by binding "{1}"

Category:
WebService

Cause:
The operation specified in binding does not appear in the corresponding port type.

Action:
Verify the binding operation. Ensure that it is specified in the corresponding port type in the WSDL.

OWS-00322
input message of binding operation "{0}" does not have a SOAP body extension

Category:
WebService

Cause:
The input message of the binding operation does not have a SOAP body extension.

Action:
Verify that the SOAP body extension 'soap:body' is properly specified in the input message of the binding operation in the WSDL.

OWS-00323
output message of binding operation "{0}" does not have a SOAP body extension

Category:
WebService

Cause:
The output message of a binding operation does not have a SOAP body extension.

Action:
Verify that the SOAP body extension 'soap:body' is properly specified in the output message of the binding operation in the WSDL.

OWS-00324
input message of binding operation "{0}" must specify a value for the "namespace" attribute

Category:
WebService

Cause:
The soap request body of the input message of a binding operation must specify a value for the namespace attribute.

Action:
Verify that the namespace attribute is properly specified in the soap request body of the input message of this binding operation in the WSDL.

OWS-00325
output message of binding operation "{0}" must specify a value for the "namespace" attribute

Category:
WebService

Cause:
The soap request body of the output message of a binding operation must specify a value for the namespace attribute.

Action:
Verify that the namespace attribute is properly specified in the soap request body of the output message of this binding operation in the WSDL.

OWS-00326
fault "{0}" in operation "{1}" matches more than one fault in the corresponding port type operation

Category:
WebService

Cause:
The fault in a binding operation matches more than one fault in the corresponding port type operation.

Action:
Verify the exact correspondence between the fault name in the binding operation and in the port type operation of the WSDL.

OWS-00327
fault "{0}" in operation "{1}" does not match any fault in the corresponding port type operation

Category:
WebService

Cause:
The fault in a binding operation does not match any fault in the corresponding port type operation.

Action:
Verify the the correspondence between the fault name in the binding operation and in the port type operation of the WSDL.

OWS-00328
fault "{0}" in operation "{1}" does not have a SOAP fault extension

Category:
WebService

Cause:
The fault in a binding operation does not have a SOAP fault extension.

Action:
Verify that the SOAP fault extension 'soap:fault' is properly specified in this fault of the binding operation.

OWS-00329
fault "{0}" refers to message "{1}", but the message has no parts

Category:
WebService

Cause:
The fault refers to a message in definitions, but the message has no parts.

Action:
Verify and ensure the fault message with properly specified part name in the WSDL.

OWS-00330
fault "{0}" refers to message "{1}", but the message has more than one parts

Category:
WebService

Cause:
The fault refers to a message in definitions, but the message has more than one parts.

Action:
Verify and correct the fault message with properly and exactly specified part name in the WSDL.

OWS-00331
in message "{0}", part "{1}" must specify a "type" attribute

Category:
WebService

Cause:
In this WSDL, there is part must specify a type attribute in message.

Action:
Verify the message in WSDL to ensure some part which also need a type definitions.

OWS-00332
in message "{0}", part "{1}" must specify an "element" attribute

Category:
WebService

Cause:
In this WSDL, there is part in message must specify an element attribute.

Action:
Verify the message in WSDL to ensure some part which also need an element definitions.

OWS-00334
the following naming conflicts occurred: {0}

Category:
WebService

Cause:
There are naming conflicts occurred in WSDL.

Action:
Verify the naming in WSDL is properly and correctly without conflict.

OWS-00335
Unsupported DIME layout: {0}

Category:
WebService

Cause:
The DIME message layout specified in the operation is not supported.

Action:
Verify and check the DIME layout specified. The supported layout are: closed-layout and open-layout.

OWS-00336
binding "{0}" uses both streaming attachments and mime-multipart

Category:
WebService

Cause:
There is binding which uses both streaming attachments and mime-multipart in WSDL.

Action:
Verify and correct the WSDL binding to ensure not both streaming attachments and mime-multipart is used.

OWS-00337
binding "{0}" uses both streaming attachments and DIME

Category:
WebService

Cause:
There is binding which uses both streaming attachments and DIME message in WSDL.

Action:
Verify and correct the WSDL binding to enusre not both streaming attachments and DIME is used.

OWS-00338
<portType> definition is not found in the WSDL

Category:
WebService

Cause:
There is no service and portType definition found in the WSDL.

Action:
Verify and check the WSDL. Either service or portType has to be defined and specified.

OWS-00339
IO error in processing schemas: {0}

Category:
WebService

Cause:

Action:

OWS-00340
The value of service-interface {0} MUST be package qualified. It is changed to {1}.

Category:
WebService

Cause:

Action:

OWS-00341
unrecognized type encountered: {0}

Category:
WebService

Cause:

Action:

OWS-00342
exception occurred while processing type {0}, {1}

Category:
WebService

Cause:

Action:

OWS-00343
Service "{0}" does not contain any usable ports

Category:
WebService

Cause:
There is no port in the current WSDL that is suitable for JAXRPC based proxy generation.

Action:
Correct the WSDL, based on the other error or warning provided, so that there is one port in the current WSDL suitable for JAXRPC based proxy generation.

OWS-00344
Port "{0}" does not contain any usable operations

Category:
WebService

Cause:

Action:

OWS-00345
ignoring port "{0}": because it references "{1}" that does not contain a SOAP Binding. Only soap:binding is supported.

Category:
WebService

Cause:

Action:

OWS-00346
ignoring port "{0}": no SOAP address specified

Category:
WebService

Cause:
The "service/port" element is missing a required child element for SOAP binding: "soap:address".

Action:
Add the missing element in the original WSDL or using a local copy if you do not own the service endpoint.

OWS-00347
ignoring operation "{0}": not request-response or one-way

Category:
WebService

Cause:

Action:

OWS-00348
ignoring RPC-style operation "{0}": parameters are not encoded

Category:
WebService

Cause:

Action:

OWS-00349
ignoring operation "{0}": message part does not refer to a schema element declaration or refers to a schema type declaration without specifiying the name attribute.

Category:
WebService

Cause:

Action:

OWS-00350
ignoring header "{0}" of binding operation "{1}". This header must be mapped to a parameter using a jaxrpc mapping file or the information in the header will be ignored at runtime.

Category:
WebService

Cause:

Action:

OWS-00351
ignoring header "{0}" of binding operation "{1}": not literal

Category:
WebService

Cause:

Action:

OWS-00352
ignoring header "{0}" of binding operation "{1}": not SOAP-encoded

Category:
WebService

Cause:

Action:

OWS-00353
ignoring header "{0}" of operation "{1}": its type is not constant across all operations in this port

Category:
WebService

Cause:

Action:

OWS-00354
ignoring MIME part "{0}" of operation "{1}": either the part was not found in the specified message or the "mimePartToParameter" flag was set to false.

Category:
WebService

Cause:

Action:

OWS-00355
value type package prefix is ignored for the types defined in the schema that has same target namespace as the target namespace of WSDL: "{0}"

Category:
WebService

Cause:

Action:

OWS-00356
binding "{0}" is ignored because it has an invalid attribute: transport="{1}"

Category:
WebService

Cause:
The value of the transport attribute on the soap:binding element is not recognized. The SOAP1.1 value is "http://schemas.xmlsoap.org/soap/http".

Action:
Correct the value of the transport attribute in the original WSDL or use a local copy if you do not own the service endpoint.

OWS-00357
ignoring document-style operation "{0}": parameters are not literal

Category:
WebService

Cause:
The value for the "use" attribute on document-style binding is invalid. the only value supported is "literal".

Action:
Correct the original WSDL or use a local copy if you do not own the service endpoint.

OWS-00358
ignoring operation "{0}": input message with multiparts is not WS-I compliant and is not currently supported

Category:
WebService

Cause:
The wsdl:message referenced by the portType/operation/input element contains more than one part and doesnt comply with WS-I BP 1.1.

Action:
If you have control over the WSDL, changes the message style for bare to wrapped, so that the WSDL comply with WS-I profile. Otherwise, use the SAAJ APIs to invoke the service without to use JAXRPC generated proxy.

OWS-00359
ignoring operation "{0}": output message with multiparts is not WS-I compliant and is not currently supported

Category:
WebService

Cause:
The wsdl:message referenced by the portType/operation/output element contains more than one part and doesnt comply with WS-I BP 1.1.

Action:
If you have control over the WSDL, changes the message style for bare to wrapped, so that the WSDL comply with WS-I profile. Otherwise, use the SAAJ APIs to invoke the service without to use JAXRPC generated proxy.

OWS-00360
The WSDL used has operations with literal and encoded use. -f:searchschema is not supported for this scenario.

Category:
WebService

Cause:
The WSDL has soapbinding subelements with use="literal" as well as use="encoded". Searching of Schema is not supported for this scenario.

Action:
Modify the WSDL to have only use="literal" or use="encoded"

OWS-00361
ignoring fault "{0}" of operation "{1}", part name "{2}" is not unique

Category:
WebService

Cause:
The WSDL uses the fault partname more than once.

Action:
Update WSDL to specify unique fault part name.

OWS-00362
Notification operation "{0}" in binding "{1}" is not supported.

Category:
WebService

Cause:
Notification operations are not supported.

Action:
Use a WSDL with no notification operations.

OWS-00363
Non conforming WSI WSDL used for wsdl:import

Category:
WebService

Cause:
WSDL import element doesnt comply with WS-I

Action:
Update the WSDL so that the imports precede all other top level elements in the WSDL.

OWS-00364
Non conforming WSI WSDL used for wsdl:types

Category:
WebService

Cause:
WSDL types element doesnt comply with WS-I

Action:
Update the WSDL so that the wsdl:types elements appear immediately after the wsdl:imports or if no imports are present wsdl:types should be the first top level element.

OWS-00365
parts "{0}" not found in the message "{1}", wrong WSDL

Category:
WebService

Cause:
The part defined in the input soap body of the binding is not specified in the input message of the operation in the port type. The part defined in the output soap body of the binding is not specified in the output message of the operation in the port type.

Action:
Make sure all the parts that are defined in the input soap body of the binding are defined in the input message of the corresponding operation of the port type. make sure all the parts that are defined in the output soap body of the binding are defined in the output message of the corresponding operation of the port type.

OWS-00366
Custom mappings for rpc-encoded web service is not supported (operation = "{0}").

Category:
WebService

Cause:
the WSDL uses custom mappings and rpc encoded webservices.

Action:
If WSDL has rpc encoded bindings do not specify custom serializers. "schema" argument to Web Services Assembler along with a message format of rpc encoded is not allowed. <type-mapping> in the oracle-webservices.xml is also not allowed with rpc encoded webservices.

OWS-00367
a class by name : "{0}" is already available in the classpath

Category:
WebService

Cause:

Action:

OWS-00368
failed to make an unique serializer class : "{0}" , the error :"{1}"

Category:
WebService

Cause:

Action:

OWS-00369
failed to find accessor method "{0}" in Java type "{1}"

Category:
WebService

Cause:

Action:

OWS-00370
model is missing

Category:
WebService

Cause:
The system is missing a model.

Action:
System Internal Error - Contact Oracle Support Services

OWS-00371
Ignoring Unique Schema Constraint

Category:
WebService

Cause:
The schema used by the WSDL has a unique constraint.

Action:
Remove unique constraint

OWS-00372
The key element has not been implemented

Category:
WebService

Cause:
The WSDL uses the unsupported "key" schema element.

Action:
Modify the schema to remove the key element

OWS-00373
Model group definition has not been implemented

Category:
WebService

Cause:
The WSDL uses a schema with a model group definition

Action:
Modify the schema to remove the model group definition

OWS-00374
Substitution Group Attribute has not been implemented

Category:
WebService

Cause:
The WSDL references a schema that uses the substitutionGroup facility.

Action:
Modify the schema to remove the substitutionGroup element

OWS-00375
Block attribute has not been implemented

Category:
WebService

Cause:
The WSDL refers to a schema that uses an unsupported block attribute.

Action:
Update your schema to set "" or #all as values for the block attribute. All other values are unsupported.

OWS-00377
Base attribute must be specified in restriction tag.

Category:
WebService

Cause:
The base attribute is not specified in the restriction tag.

Action:
Specify a base type from which the complex type is to be derived by restriction.

OWS-00378
Enumeration {0} is not supported

Category:
WebService

Cause:
The enumeration is not supported.

Action:
Modify the schema to remove this enumeraton.

OWS-00379
Attribute restriction is not supported

Category:
WebService

Cause:
The base type has an attribute element with the use="prohibited".

Action:
Remove the use="prohibited" attribute on the base type.

OWS-00380
Group Schema Element has not been implemented

Category:
WebService

Cause:
The "group" schema element is not supported

Action:
Modify the schema to remove the group element

OWS-00381
Unsupported Schema Element

Category:
WebService

Cause:
Facets are not supported in the extension and restriction elements.

Action:
Remove facets (elements like xsd:pattern, xsd:minInclusive etc which restrict values of an element) from your schema.

OWS-00382
Invalid value ({0}) for "minOccurs" attribute of element - {1}. Setting value to 0.

Category:
WebService

Cause:
Invalid "minOccurs" attribute value. Setting value to 0.

Action:
Set minOccurs to 0 if the assoicating element is optional. Otherwise, set the value to 1 or more.

OWS-00383
The "maxOccurs" attribute of the {0} element has an unsupported value of {1}. Currently only boundless arrays are supported. maxOccurs must be 0,1 or unbounded. Setting to default value of "unbounded".

Category:
WebService

Cause:
Invalid or unsupported "maxOccurs" attribute value. Setting value to 0.

Action:
Set this value to a positive integer or unbounded to indicate there is no maximum number of occurrences.

OWS-00384
Value ({0}) for "final" attribute of element -{1} is currently not supported. This attribute is ignored.

Category:
WebService

Cause:
Unsupported final attribute value. Ignore the attribute.

Action:
Set this value to "#all" or ""

OWS-00386
sender error: {0}

Category:
WebService

Cause:
Invalid configuration in oracle-webservices.xml or wsmgmt.xml.

Action:
Verify the configuration setting in oracle-webservices.xml and/or wsmgmt.xml.

OWS-00387
missing body information

Category:
WebService

Cause:
SOAP Body is missing in the request. The SOAP message was not sent.

Action:
Verify request.getBody() returns a SOAP body instance.

OWS-00388
illegal value of "mustUnderstand" attribute: "{0}"

Category:
WebService

Cause:
Response contains illegal value of "mustUnderstand" attribute.

Action:
Verify the response SOAP message. Attribute "mustunderstand" must have a value of "0", "1", "true", or "false".

OWS-00389
unrecognized operation (code: {0})

Category:
WebService

Cause:
The SOAP message is invalid. It cannot be resolved to an operation's request or response.

Action:
Regenerate the stub using either Jdeveloper or the Web Service Assembler tool.

OWS-00390
unrecognized fault block

Category:
WebService

Cause:
The response fault is invalid.

Action:
Verify the content of the fault response.

OWS-00391
received empty response

Category:
WebService

Cause:
No SOAP Message is returned from the server.

Action:
Verify the corresponding WSDL operation is not oneWay.

OWS-00392
stub was not initialized

Category:
WebService

Cause:
The initialize() method of the stub was not invoked.

Action:
Regenerate the stub using either JDeveloper or the Web Service Assembler tool. If problem persists, contact Oracle Support Services.

OWS-00395
XML reader internal error: illegal state ({0})

Category:
WebService

Cause:
XMLReader encounters an XML element that cannot be deserialized.

Action:
Validate the XML document.

OWS-00396
XML reader error: unexpected character content: "{0}"

Category:
WebService

Cause:
XMLReader encounters an element with an unexcpected character content.

Action:
Validate the XML document.

OWS-00397
XML reader error: {0}

Category:
WebService

Cause:
XMLReader cannot close the reading stream.

Action:
Check network connection and file system connection.

OWS-00398
XML parsing error: {0}

Category:
WebService

Cause:
XMLReader cannot read the next element.

Action:
Validate the XML document.

OWS-00400
XML writer error: no prefix for URI: "{0}"

Category:
WebService

Cause:
No prefix is specified for the URI.

Action:
System Internal Error - Contact Oracle Support Services

OWS-00401
XML writer error: {0}

Category:
WebService

Cause:
XML Writer encounters an IOException.

Action:
Check network connection and file system connection.

OWS-00403
unexpected XML reader state. expected: {0} but found: {1}

Category:
WebService

Cause:
The XML document does not have the expected start or end of an element.

Action:
Check if any required element is missing or there are more elements where an end tag was expected.

OWS-00405
unrecognized operation: {0}

Category:
WebService

Cause:
The soap operation is not valid.

Action:
Check the operation name in the message and correct it.

OWS-00406
cannot dispatch ambiguous operation: {0}

Category:
WebService

Cause:
The specified operation is overloaded.

Action:
Remove the overloading by renaming one of the conflicting operations.

OWS-00407
unexpected header block: "{0}"

Category:
WebService

Cause:
The QName of the header block is not correct.

Action:
Correct the header block by verifying its namespace.

OWS-00408
invalid SOAP envelope: body is empty

Category:
WebService

Cause:
The body of the soap message is empty.

Action:
Provide the write content in the body element of the soap message.

OWS-00409
invalid SOAP envelope: body is missing

Category:
WebService

Cause:
The body element is either missing or its namespace is wrong.

Action:
Add the body if missing or correct the namespace of the body element.

OWS-00410
env:Body must be present in a SOAP 1.2 envelope

Category:
WebService

Cause:
The body element is missing from the message. SOAP 1.2 requires that the env:Body element must be present.

Action:
Add the soap body in the message.

OWS-00411
invalid SOAP envelope content

Category:
WebService

Cause:
The content of the soap envelope is invalid.

Action:
Correct the content of the soap envelope.

OWS-00412
invalid SOAP envelope

Category:
WebService

Cause:
The root element of the message is not a soap envelope.

Action:
Make the root element a valid soap envelope.

OWS-00413
SOAP envelope version mismatch

Category:
WebService

Cause:
The namespace or the version of the envelope is not correct.

Action:
Correct the namespace of the soap envelope.

OWS-00414
Caught exception while handling request: {0}

Category:
WebService

Cause:
Refer to the details of the message for further information on possible causes.

Action:
Refer to the details of the message for further information on possible actions.

OWS-00415
Caught exception while preparing response: {0}

Category:
WebService

Cause:
Refer to the details of the message for further information on possible causes.

Action:
Refer to the details of the message for further information on possible actions.

OWS-00416
Caught exception while invoking the post handling hook: {0}

Category:
WebService

Cause:
Refer to the details of the message for further information on possible causes.

Action:
Refer to the details of the message for further information on possible actions.

OWS-00417
Internal Server Error ({0})

Category:
WebService

Cause:
Refer to the details of the message for further information on possible causes.

Action:
Refer to the details of the message for further information on possible actions.

OWS-00418
Could not find the field in the Holder that contains the Holder value: {0}

Category:
WebService

Cause:
Refer to the details of the message for further information on possible causes.

Action:
Refer to the details of the message for further information on possible actions.

OWS-00420
No jar file (or directory) found at specified path: {0}

Category:
WebService

Cause:
The specified jar file does not exist.

Action:
Check if the jar file name is correct and it is in the right directory.

OWS-00422
Exception occured while verifiying EJB: Class: {0} Details: {1}

Category:
WebService

Cause:
Error while parsing ejb-jar.xml. Refer to the details of the message for further information on possible causes.

Action:
Refer to the details of the message for further information on possible actions.

OWS-00423
The EJB {0} was not found in the specified ejb location

Category:
WebService

Cause:
The ejb-jar.xml does not contain the specified EJB.

Action:
Check if the name of the EJB is correct and it is present in the ejb-jar.xml.

OWS-00425
Unable to locate ejb-jar.xml in {0}

Category:
WebService

Cause:
The application does not contain an ejb-jar.xml deployment descriptor file. The deployment descriptor file is inspected to locate the endpoint service interface

Action:
Add ejb-jar.xml and reassemble the application.

OWS-00426
Error parsing ejb-jar.xml. No session beans found.

Category:
WebService

Cause:
The application does not contain any session bean definition. The business functions to be exposed as webservices should be defined in a session bean.

Action:
Write an Enterprise Java Session Bean that contains the business functions that you want to expose.

OWS-00427
Error parsing ejb-jar.xml. Stateful session beans are not supported.

Category:
WebService

Cause:
Creating webservices from a stateful session bean is not supported. The business functions to be exposed as webservices should be defined in a stateless session bean.

Action:
Remove the stateful session bean, write a stateless session bean that contains the business functions that you want to expose.

OWS-00432
ERROR: {0}

Category:
WebService

Cause:
Server or client artifacts generation has failed.

Action:
This is a generic error indicating an error condition. You should also see a message describing the details.

OWS-00433
WARNING: {0}

Category:
WebService

Cause:
Server or client artifacts generation has encountered a possible error.

Action:
This is a generic warning. You should also see a message describing the details.

OWS-00436
-import requires a WSDL-based configuration file

Category:
WebService

Cause:

Action:

OWS-00437
-define requires a service-based configuration file

Category:
WebService

Cause:

Action:

OWS-00439
You have specified : -gen:both or -gen:client with SEI. The use of these modes are recommended with WSDL only.

Category:
WebService

Cause:

Action:

OWS-00442
Problem validating implementation class. {0}

Category:
WebService

Cause:
Supplied Service implementation class is not valid. It could be that the implementation class does not implement the interface correctly or it does not conform to JAXRPC requirements or the class is not found.

Action:
Make sure the implementation class is JAXRPC compliant if it is a JAXRPC webservice; make sure the classpath containing the implementation class is correctly specified

OWS-00450
parsing failed: {0}

Category:
WebService

Cause:
SAXException is thrown from the parser while parsing the WSDL.

Action:
Fix the WSDL according to the error reported by the parser.

OWS-00451
parsing failed: {0}

Category:
WebService

Cause:
ParserConfigurationException is thrown from the parser while parsing the WSDL.

Action:
Unexpected internal error.

OWS-00460
Element type "{1}" is missing required attribute "{0}"

Category:
WebService

Cause:
The WSDL or Schema entity is missing the required attribute.

Action:
Add the required attribte with a valid value to the WSDL or Schema entity.

OWS-00461
Element named "{0}" of type "{2}" is missing required attribute "{1}"

Category:
WebService

Cause:
The WSDL or Schema entity is missing the required attribute.

Action:
Add the required attribte with a valid value to the WSDL or Schema entity.

OWS-00463
missing required sub-entity "{0}" of element "{1}"

Category:
WebService

Cause:
A sub-element required by the schema or WSDL specification is missing.

Action:
Modify the schema or WSDL to add the required sub-element.

OWS-00464
Could not find Attribute : "{0}"

Category:
WebService

Cause:
An attribute reference is not defined in the schema.

Action:
Modify the schema to define the missing attribute reference.

OWS-00465
Unsupported schema feature : "{0}"

Category:
WebService

Cause:
An element defined in the schema is not supported by the system.

Action:
Modify the schema.

OWS-00466
The element is not supported in this context : "{0}"

Category:
WebService

Cause:
A sub-element of the complex type extension/restriction definition in the schema is not supported by the system.

Action:
Modify the complex type extension/restriction definition in the schema.

OWS-00467
Unsupported simple type definition : "{0}" inside "{1}" element

Category:
WebService

Cause:
A simple type defined in the schema is not supported by the system.

Action:
Modify the simple type to a simple type supported by the system.

OWS-00468
invalid sub-element "{0}" of element "{1}"

Category:
WebService

Cause:
The WSDL contains an element with a sub-element that is not supported by the system. Check WSDL 1.1 specification.

Action:
Modify the invalid sub-element based on the WSDL 1.1 specification.

OWS-00469
invalid attribute "{0}" of element "{1}"

Category:
WebService

Cause:
The WSDL or schema contains an element with an attribute that is either formatted incorrectly or does not comply with the specifications support by the system. The specifications to check include SOAP, WSDL 1.1 and jaxrpc.

Action:

OWS-00470
invalid value "{1}" for attribute "{0}"

Category:
WebService

Cause:
A attribute on a WSDL or schema element has a value that is not expected by the system.

Action:
or WSDL to comply with the value for the schema type of the attribute or change the type of the attribute to a simple type like string or int.

OWS-00471
invalid range found (min: {0}, max: {1})

Category:
WebService

Cause:
A complex type in a schema defines min and max occurance on a type that the system does not support.

Action:
Change the max occurances attribute to 1 so the system will except the schema.

OWS-00472
exclusive attributes: "{0}", "{1}"

Category:
WebService

Cause:
A complex type in a schema defines two attributes that are not supposed to be defined at the same time.

Action:
Remove one of the specified attriubutes from the schema.

OWS-00474
not a simple type: "{0}"

Category:
WebService

Cause:
A schema type other than a simple type was found in a schema when a simple type is expected.

Action:
Change the type specified in the error message to a simple schema type or change the reference to this type to a simple schema type.

OWS-00475
port type "{0}" in binding "{0}" not found.

Category:
WebService

Cause:
The specified WSDL is invalid or complete. A binding in a WSDL document has a reference to a portType that is not defined in the WSDL.

Action:
Change the value of the type attribute in the binding to the name of a portType that is defined in the WSDL.

OWS-00476
message "{0}" not found.

Category:
WebService

Cause:
The specified WSDL is invalid or complete. An input, output or fault element has a value for the message attribute that is not defined in the WSDL.

Action:
Change the value of the message attribute to a message that is defined in the WSDL.

OWS-00477
type "{0}" defined for the message part "{1}" could not found.

Category:
WebService

Cause:
The type definition is not found in the schema.

Action:
Add the type definition to the schema, or change the value of the type attribute to the name of an existing schema type.

OWS-00478
element "{0}" defined for the message part "{1}" could not found.

Category:
WebService

Cause:
A schema contains a reference to an element name that does not exist in the specified set of schemas. The set of schemas can be inside of a WSDL document, imported from a WSDL document or imported from other schema documents.

Action:
Change the reference to an element name that is found in the specified set of schemas, or define the type in the schema.

OWS-00480
Binding "{1}" used in port "{0}" not found.

Category:
WebService

Cause:
The specified WSDL is invalid or complete. A port in the WSDL document has a reference to a binding that is not defined in the WSDL.

Action:
Change the value of the binding attribute in the port to the name of a binding that is defined in the WSDL, or define the binding.

OWS-00481
The name "{0}" is not a valid XML NCName. (see http://www.w3.org/TR/1999/REC-xml-names-19990114/#NT-NCName)

Category:
WebService

Cause:
The name is not a valid XML NCName.

Action:
Correct the value of NCName. See http://www.w3.org/TR/1999/REC-xml-names-19990114/#NT-NCName for the format.

OWS-00482
The extensibility element "{0}" is unknown and has a wsdl:required attribute set to "true"

Category:
WebService

Cause:
During WSDL validation, found unrecognized extensibility element with wsdl:required attribute set.

Action:
Ensure required extension registry is set with WSDLReader when reading WSDL document into WSDL definition or remove wsdl:required attribute

OWS-00483
The WSDL contains a mixture of styles - "document" and "rpc". Only "rpc" OR "document" is supported in a WSDL, not both.

Category:
WebService

Cause:
WSDL contains a mixture of styles i.e both "Document" and "Rpc" style operation

Action:
Multiple styles WSDL is not supported by JAXRPC/JAXWS. Make sure WSDL does not contain muplitple styles i.e both document and rpc style bidning operation.

OWS-00484
The WSDL contains a mixture of uses - "literal" and "encoded". Only "literal" OR "encoded" is supported in a WSDL, not both.

Category:
WebService

Cause:
WSDL contains both "literal" and "encoded" use

Action:
Make sure WSDL does not contain mixture of uses - "literal" and "encoded". Only "literal" or "encoded" is supported in a WSDL, not both

OWS-00485
Operation "{0}" and "{1}" have conflicting SOAPAction values. Do not overload any operation or give unique SOAPAction value to each operation binding.

Category:
WebService

Cause:
Two or more operations specified in WSDL have conflicting SOAPAction values.

Action:
Do not overload any operation or give unique SOAPAction value to each operation binding.

OWS-00486
Operation "{0}" does not have a SOAPAction value. Give it a unique value.

Category:
WebService

Cause:
In WSDL, overloaded operation does not contain SOAPAction value.

Action:
Specify unique SOAPAction value for the overloaded operation.

OWS-00487
Element does not have name

Category:
WebService

Cause:
Element declared in schema does not have a "name" attibute set.

Action:
Specify a name to an Element defined in a schema.

OWS-00488
Attribute group does not have name

Category:
WebService

Cause:
Attribute group does not contain any name.

Action:
Specify a name to an attribute group.

OWS-00490
AttributeGroup "{0}" child missing ref attribute.

Category:
WebService

Cause:
Child element of Attirbute group is missing "ref" attribute.

Action:
Specify a name to a child element of Attibute group.

OWS-00491
Attribute declaration missing name.

Category:
WebService

Cause:
In schema, attirbute declaration is missing name.

Action:
Provide valide "name" to the attribute declaration.

OWS-00492
AttributeGroup missing ref attribute

Category:
WebService

Cause:
During schema validation, found AttributeGroup element is missing "ref" attribute.

Action:
Make sure AttributeGroup has "ref" attribute declared.

OWS-00493
Warning: {0} is already defined. Ignoring.

Category:
WebService

Cause:

Action:

OWS-00494
The portType {0} is used by two bindings with different headers mapped to parameters. This usecase is not supported at this time. Map the same headers to parameters for all bindings using this port type.

Category:
WebService

Cause:
The portType defined in WSDL is used by two bindings with different headers mapped to parameters.

Action:
Map the same headers to parameters for all bindings using this port type.

OWS-00495
The specified service name "{0}" was not found.

Category:
WebService

Cause:
In WSDL, service element does not have "name" attirbute defined.

Action:
Make sure WSDL has valid service name.

OWS-00496
Error while loading the schemas defined in WSDL "{0}": "{1}"

Category:
WebService

Cause:
Failed to load the schema specified in the WSDL.

Action:
Ensure the schema location specified in the WSDL is correct.

OWS-00499
LiteralArrayWrapper may only have one element member.

Category:
WebService

Cause:
LiteralArrayWrapper has more than one element member.

Action:
Make sure LiteralArayWrapper contains one element member.

OWS-00500
The annotation type or property "{0}" has been deprecated in this version of Oracle WebServices.

Category:
WebService

Cause:

Action:

OWS-00502
The annotations on the impl bean {0} or a referenced SEI are not consistent with the portType(s), binding(s) and service(s) in the WSDL specified by the wsdlLocation: {1}. Please refer to section 4.1.1 of the JSR-181 specification for details on the usage of wsdlLocation. The {2} was not found in the WSDL.

Category:
WebService

Cause:
The WSDL specified by a wsdlLocation attribute is inconsistent with the portType and bindings declared in the same WSDL.

Action:
Ensure that the annotations are consistent with the WSDL. See section 4.1.1 of the JSR-181 spec.

OWS-00505
Not a java bean

Category:
WebService

Cause:
The specified value type is not a valid Java Bean.

Action:
Ensure that the all declared value types are valid Java Bean.

OWS-00506
Not a java bean. Class is not public.

Category:
WebService

Cause:
The specified class is not a valid Java Bean.

Action:
Ensure the specified class has "public" modifier.

OWS-00526
Not in class path

Category:
WebService

Cause:
The specified class could not found in classpath.

Action:
Ensure that all required classes or jar files containing classes are declared in classpath.

OWS-00527
Element "{0}" can not have both a type attribute and a nested type declaration.

Category:
WebService

Cause:
The WSDL or schema contains an element with a type attribute and a nested type defined.

Action:
None

OWS-00528
Type "{0}" is not a valid JAXRPC value type or it is not serializable.

Category:
WebService

Cause:
SEI contains method with unserializable return type or parameter type

Action:
Ensure that all parameter types and return type are valid value types as per JAXRPC specification.

OWS-00530
WSDL is not WS-I BP compliant. Literal style WSDL at location "{0}" can not have soap encoded type.

Category:
WebService

Cause:
Invalid WSDL. Provided WSDL has both literal and soap encoding style.

Action:
Make sure WSDL has either "literal" or "encoding" style, NOT both

OWS-00531
Could not find schema from URL source, file source, classpath or application context at this lcoation: "{0}"

Category:
WebService

Cause:
Could not locate the schema document from file, url, classpath or application context.

Action:
Verify that the specified location of schema is correct.

OWS-00532
Failed to retrieve policy

Category:
WebService

Cause:
Could not retrieve the policy from the Policy Accessor.

Action:
System Internal Error - Contact Oracle Support Services

OWS-00533
Value {0} is not valid for {1}

Category:
WebService

Cause:
Invalid value encountered while deserializing a Java value from XML.

Action:
Verify that XML datatype contains valid value as per the schema.

OWS-00536
The output of a binding operation "{0}" is missing

Category:
WebService

Cause:
The output of a binding operation is missing.

Action:
Verify that the output element is properly specified in the binding operation in the WSDL.

OWS-00537
The input element, under namespace of "http://schemas.xmlsoap.org/wsdl/", of the binding operation "{0}" is missing

Category:
WebService

Cause:
The input element, under namespace of "http://schemas.xmlsoap.org/wsdl/", of a binding operation is missing.

Action:
Verify that the input element is properly specified in the binding operation in the WSDL.

OWS-00538
The value of the BindingType annotation "{0}" does not match the SOAP version "{1}" on the WSDL.

Category:
WebService

Cause:
The value of the BindingType annotation does not match the SOAP version on the WSDL.

Action:
Verify the value of the BindingType annotation.

OWS-00539
The WebParam or WebResult annotation on method "{0}" does not match the WSDL or Schema; The "{1}" "{2}" element is missing.

Category:
WebService

Cause:
The WebParam or WebResult annotation does not exist, or does not match the WSDL/Schema.

Action:
Verify the value of the WebParam or WebResult annotation.

OWS-00542
Unable to initialize, missing WebServicesProcessor

Category:
WebService

Cause:
Unable to initialize interceptors due to missing WebService Processor

Action:
System Internal Error - Contact Oracle Support Services

OWS-00543
Unable to provision web service, cannot read WSDL. Error: {0}

Category:
WebService

Cause:
Could not read WSDL.

Action:
Check the WSDL URL for correctness and try again or check the server logs for details.

OWS-00544
Error destroying interceptors {0}

Category:
WebService

Cause:

Action:

OWS-00545
Unable to read SOAP message {0}

Category:
WebService

Cause:

Action:

OWS-00546
Invalid port configuration {0}

Category:
WebService

Cause:

Action:

OWS-00547
{0}

Category:
WebService

Cause:

Action:

OWS-00549
The WSDL has overloaded operations "{0}".

Category:
WebService

Cause:
The WSDL has overloaded operations.

Action:
Avoid using overloaded operations.

OWS-00550
JDK1.5 enum is not supported "{0}".

Category:
WebService

Cause:
JDK1.5 enum is not supported

Action:
Provide a custom seriallizer.

OWS-00551
You are running on JDK6 which comes with JAX-WS 2.1 API and JAXB 2.2 API, but this tool requires JAX-WS 2.2 API and JAXB 2.2.1 API. Use the endorsed standards override mechanism (http://java.sun.com/javase/6/docs/technotes/guides/standards/).

Category:
WebService

Cause:
JDK 1.6 not configured correctly for JAX-WS

Action:
Provide an endorsed folder with the newer jars

OWS-03002
Failed to load wsm config schema: {0}

Category:
WebService

Cause:
Failed to load wsm config schema.

Action:
Please check the WSM configuration schema.

OWS-03003
{0}

Category:
WebService

Cause:

Action:

OWS-03004
{0}

Category:
WebService

Cause:
An exception occured while webservice management configuration.

Action:
Verify that the oracle proprietary descriptor for configuration is valid xml file and confirms to the schema "http://xmlns.oracle.com/oracleas/schema/11/oracle-webservices-client-11_1.xsd"

OWS-03005
Unable to connect to URL: {0} due to {1}

Category:
WebService

Cause:

Action:

OWS-03009
Error reading client wsmgmt configuration {0}

Category:
WebService

Cause:
Unexpected error occurs while reading client configuration file

Action:
NONE

OWS-03010
Error creating default client wsmgmt configuration {0}

Category:
WebService

Cause:
Unexpected error occured while creating default client side configuration file

Action:
System Internal Error - Contact Oracle Support Services

OWS-03011
Error parsing client wsmgmt configuration file {0}

Category:
WebService

Cause:

Action:

OWS-03012
Error parsing client wsmgmt configuration file {0}

Category:
WebService

Cause:

Action:

OWS-03013
Error parsing client wsmgmt configuration file {0}

Category:
WebService

Cause:
Unexpected error occured while parsing client webservice management configuration file

Action:
Verify that client side configuration file is a valid xml file

OWS-03014
Error loading policy access cache configuration {0}

Category:
WebService

Cause:
Policy access cache configuration file could not be loaded due to unexpected error

Action:
System Internal Error - Contact Oracle Support Services

OWS-03015
Error accessing policy from cache {0}

Category:
WebService

Cause:
Accessing policy from cache is failed

Action:
System Internal Error - Contact Oracle Support Services

OWS-03016
Error loading interceptor class {0}

Category:
WebService

Cause:
Failed to looad the Inteceptor class

Action:
Ensure all required webservices client side jar files available in classpath

OWS-04007
Error in system configured ejb prehandler: {0}

Category:
WebService

Cause:

Action:

OWS-04011
Error in resolving the webservice endpoint: {0}

Category:
WebService

Cause:
Failed to determine the WebService Endpoint for the servlet

Action:
None

OWS-04014
Error in system configured servlet post-handler: {0}

Category:
WebService

Cause:

Action:

OWS-04018
Error processing soap message over jms :{0}

Category:
WebService

Cause:

Action:

OWS-04020
Error during handler invocation:

Category:
WebService

Cause:

Action:

OWS-04024
Error in system configured ejb post-handler: {0}

Category:
WebService

Cause:

Action:

OWS-04026
An I/O error occurred for port: {0}: {1}.

Category:
WebService

Cause:
An unexpected IO error occured while processing service request.

Action:
None

OWS-04029
Error in system configured servlet pre-handler: {0}

Category:
WebService

Cause:

Action:

OWS-04039
Error closing connection: {0}

Category:
WebService

Cause:
Failed to close the connection to specific database

Action:
None

OWS-04042
Error happened while loading the DDs

Category:
WebService

Cause:

Action:

OWS-04043
{0}

Category:
WebService

Cause:

Action:

OWS-04044
The referenced wsdl file has changed, please re-deploy {0}

Category:
WebService

Cause:

Action:

OWS-04045
Malformed Request Message: {0}

Category:
WebService

Cause:
Received malformed SOAP request message

Action:
Ensure the correct SOAP message constructed at client side

OWS-04046
{0} {1}

Category:
WebService

Cause:
A server side fault occured while handling the SOAP message

Action:
Please see the exception or server side log for more detail

OWS-04047
Cannot create xslt transformer

Category:
WebService

Cause:

Action:

OWS-04048
xslt transformation failed

Category:
WebService

Cause:

Action:

OWS-04050
Unable to load the webservices management interceptor pipeline

Category:
WebService

Cause:

Action:

OWS-04061
Internal JMX error {0}

Category:
WebService

Cause:
Internal error while configuring JMX

Action:
None

OWS-04062
XML parser configuartion error {0}

Category:
WebService

Cause:
An unexpected error occured while parsing configuring the XML parser

Action:
None

OWS-04065
Error creating default port configuration for interceptor {0}

Category:
WebService

Cause:
The default port configuration for interceptor could not be created

Action:
None

OWS-04066
Missing port info for service.

Category:
WebService

Cause:
The Port information for the service is missing

Action:
Add the necessary port information while configuring dynamic service.

OWS-04067
Error reading config file {0}

Category:
WebService

Cause:
Failed to read the interceptor configuration file

Action:
None

OWS-04068
Error serializing default config {0}

Category:
WebService

Cause:
Failed to serialize the default configuration for interceptor.

Action:
None

OWS-04069
Error serializing global configuration for {0} interceptor {1}

Category:
WebService

Cause:
Failed to serialize global configration for interceptor.

Action:
None

OWS-04070
Error serializing configuration {0}

Category:
WebService

Cause:
Failed to serialize the configuration

Action:
None

OWS-04071
Unrecognized interceptor configuration: {0}

Category:
WebService

Cause:

Action:

OWS-04072
Error writing config file {0}

Category:
WebService

Cause:
Error writing the configuration file for interceptor to FileManager

Action:
None

OWS-04073
Error parsing wsmgmt configuration file {0}

Category:
WebService

Cause:

Action:

OWS-04074
Error parsing wsmgmt configuration file {0}

Category:
WebService

Cause:

Action:

OWS-04075
Error parsing wsmgmt configuration file {0}

Category:
WebService

Cause:

Action:

OWS-04086
{0}

Category:
WebService

Cause:
An unexpected error occured

Action:
None

OWS-04092
Unable to configure parser: {0}

Category:
WebService

Cause:

Action:

OWS-04093
Unable to parse schema: {0}

Category:
WebService

Cause:

Action:

OWS-04094
unknown tag <{0}> in {1}

Category:
WebService

Cause:

Action:

OWS-04097
Error creating client default port configuration for interceptor {0}

Category:
WebService

Cause:
Failed to create client default port configuration for interceptor

Action:
None

OWS-04100
Unable to find provider port that is associated with the servlet named {0}. Please make sure <provider-name>{0}</provider-name> exists in oracle-webservices.xml.

Category:
WebService

Cause:

Action:

OWS-04101
Unable to add dynamic provider endpoint. Please make sure service name {0} and port name {1} are unique. They are specified as arguments to the ProviderConfig.addService() method or in the endpoint associated WSDL.

Category:
WebService

Cause:

Action:

OWS-04102
Unable to configure dynamic provider endpoint across cluster due to exception {0}

Category:
WebService

Cause:

Action:

OWS-04103
Unknown element <{0}> in descriptor: {1}

Category:
WebService

Cause:

Action:

OWS-04104
The oracle-webservices.xml configuration references a web service description named "{0}", but there is no web service description with that name in webservices.xml.

Category:
WebService

Cause:

Action:

OWS-04105
The final WSDL path "{0}" cannot be parsed as a URL: {1}

Category:
WebService

Cause:
The URL path for the final WSDL is not valid

Action:
Provide the valid URL location for the WSDL.

OWS-04106
The value of the element named "{0}" ({1}) in {2} is invalid. Please refer to the XML schema of this descriptor for acceptable values.

Category:
WebService

Cause:
Found invalid value of an element declared in webservice deployment descriptor

Action:
Please refer to the XML schema of this descriptor for acceptable values for this element.

OWS-04107
The proprietary implementor type is not specified.

Category:
WebService

Cause:

Action:

OWS-04108
An error was encountered while trying to write the runtime configuration for the web service endpoint named "{0}": {1}

Category:
WebService

Cause:
An error was encountered while trying to write the runtime configuration for the web service endpoint.

Action:
None

OWS-04110
Error downloading import: Invalid URL

Category:
WebService

Cause:
The specified URL for the imported WSDL is invalid

Action:
Provide the correct URL location for the WSDL import

OWS-04111
Proxy information not set, external import downloads may fail.

Category:
WebService

Cause:

Action:

OWS-04112
The policy accessor configuration could not be loaded from {0}: {1}. Using default configuration instead.

Category:
WebService

Cause:
Failed to load policy accessor configuration

Action:
No action required as incase of this, default policy accessor configuration will be used

OWS-04113
Policy advertisement failed for {0}: {1}

Category:
WebService

Cause:
Failed to advertise the policy in the WSDL

Action:
None

OWS-04115
An error occurred for port: {0}: {1}.

Category:
WebService

Cause:
A server side exception occured while processing request or creating the response message

Action:
Please see the server side log for the detail.

OWS-04116
The error stack trace: {0}

Category:
WebService

Cause:

Action:

OWS-04117
{0}

Category:
WebService

Cause:
Exception occured while configuring dynamic provider based endpoint

Action:
None

OWS-04119
Local service registration failed for {0}: {1}

Category:
WebService

Cause:

Action:

OWS-04121
Invalid use of <web-site> element in oracle-webservices.xml.<web-site> element must have two attributes "host" and "port" with valid values

Category:
WebService

Cause:
<web-site> element of oracle-webservice.xml doesn't contain 'host' and 'port' attributes with valid values

Action:
Add valid 'host' and 'port' attributes to the <web-site> element, or remove the element.

OWS-04123
Unsupported oracle-webservices deployment descriptor for module {0}, schema version {1}

Category:
WebService

Cause:

Action:

OWS-04124
Failed to register the web service Config MBeans for application: {0} endpoint: {1} the error is: {2}

Category:
WebService

Cause:
Failed to register the web service config MBeans for endpoint

Action:
None

OWS-04125
cannot find WSDL definition required to validate input

Category:
WebService

Cause:
cannot load web service WSDL definition, which is required for schema validation of input

Action:
Ensure that the WSDL is available, or set schema validation of input to false

OWS-04126
Input Violates Schema

Category:
WebService

Cause:
SOAP body element of the input message cannot be validated against schema in the WSDL

Action:
Correct input message body, input message type in the WSDL schema, or set schema validation of input to false

OWS-04127
Invalid query string

Category:
WebService

Cause:
User has specified invalid URL Query String.

Action:
Verify that the correct query string is specified for acccessing the testpage.

OWS-04128
Failed to deploy/initialize the application as given archive is missing required standard webservice deployment decriptor.

Category:
WebService

Cause:
The user suppplied war archive is missing required webservice deployment descriptor

Action:
Create WAR file with required webservice deployment descriptor or use WSA's jaxwsAssemble command to assemble the WAR file.

OWS-04130
Failed to initialize Tie class "{0}" at runtime due to Error: {1}

Category:
WebService

Cause:
Failed to initialize the tie class on server side due to classloading issue or java security.

Action:
Please look the server log for exact cause of an error.

OWS-04131
SOAP must understand error. MustUnderstand headers:["{0}"] are not understood.

Category:
WebService

Cause:
Server could not understand SOAP header which has mustUnderstand flag set to true.

Action:
Please look the SOAPFault string for any detail message and check the client and server side configuration.

OWS-04132
FastInfoset is disabled for this service

Category:
WebService

Cause:
A FastInfoset message was received for a service that has FastInfoset disabled

Action:
Please enable FastInfoset for the web service or send a non-FastInfoset input message

OWS-04136
JRF WebServices are not supported in 'Restricted JRF'.

Category:
WebService

Cause:
Trying to deploy JRF WebServices which is not supported in 'Restricted JRF'.

Action:
Use 'Full JRF' for deploying application that uses JRF WebServices implementation.

OWS-04137
DTD is not supported

Category:
WebService

Cause:
Sending SOAP request with DTD

Action:
Do not use DTD in SOAP request to JRF web services

OWS-08008
Web service artifact generation failed.

Category:
WebService

Cause:
Web service artifact generation failed.

Action:
Verify and correct by the error message and stack trace.

OWS-08010
Incorrect packaging ({0}): WSDL should be packaged in a directory named either 'META-INF/wsdl' or 'WEB-INF/wsdl'.

Category:
WebService

Cause:
Incorrect WSDL packaging.

Action:
Verify that the correct the WSDL packaging configurations.

OWS-08015
No web service named '{0}' is defined. Ignoring the proprietary configuration for this web service.

Category:
WebService

Cause:
Web service name is not properly defined.

Action:
Verify that the web service name from the proprietary configuration.

OWS-15001
An extension registry was not found for the element type "{0}"

Category:
WebService

Cause:
An extension registry was not found for an element type

Action:
None

OWS-15002
A failure occurred in loading WSDL from "{0}"

Category:
WebService

Cause:
A failure occurred in loading WSDL

Action:
Verify if the WSDL exists at the specified URL

OWS-15004
WSDL contains an operation type of "{0}" which is not supported for port type "{1}"

Category:
WebService

Cause:
WSDL contains an operation type that is not supported

Action:
Modify the WSDL and change the operation type to a supported one

OWS-15005
An error occurred when invoking the method. Type of WSIF invocation was "{1}" and method name was ("{0}")

Category:
WebService

Cause:
An error occurred when invoking the method

Action:
Check client code and network connection

OWS-15006
Multiple WSIFProvider found supporting the same namespace URI "{0}". Found ("{1}")

Category:
WebService

Cause:

Action:

OWS-15008
WSIFDefaultCorrelationService removing correlator due to timeout. ID:"{0}"

Category:
WebService

Cause:

Action:

OWS-15010
Exception thrown while processing asynchronous response - "{0}"

Category:
WebService

Cause:
Exception thrown while processing asynchronous response

Action:
None

OWS-25106
Internal error: {0}

Category:
WebService

Cause:

Action:

OWS-25108
Some messages have not been acknowledged

Category:
WebService

Cause:

Action:

OWS-25111
Error sending LastMessage: {0}

Category:
WebService

Cause:
Unknown

Action:
Check server logs for additional details.

OWS-25112
The WS-RM client interceptor encountered an exception while handling a response, {0}

Category:
WebService

Cause:

Action:

OWS-25113
Duplicate eliminated for message #{0}

Category:
WebService

Cause:

Action:

OWS-25118
Skip null in handling outbound message {0}

Category:
WebService

Cause:

Action:

OWS-25119
Forcing wsa:Action inside RM code to {0}. Please, verify your addressing handler configuration

Category:
WebService

Cause:

Action:

OWS-25168
An attempt was made to terminate a WS-RM sequence inactivity monitor for the sequence identified by {0}, which is not currently being monitored.

Category:
WebService

Cause:

Action:

OWS-50001
The @WebService.portName is not allowed on endpoint interfaces.: {0}

Category:
WebService

Cause:

Action:

OWS-50002
The @WebService.serviceName is not allowed on endpoint interfaces.: {0}

Category:
WebService

Cause:

Action:

OWS-50003
Could not find schema type : {0}

Category:
WebService

Cause:

Action:

OWS-50004
The method "{0}" does not have the AsyncHandler type parameter.

Category:
WebService

Cause:
The callback type asynchronous method that returns java.util.concurrent.Future must have the last parameter of the type AsyncHandler.

Action:
Add the last parameter of type AsyncHandler in the method, or regenerate the interface using wsa tool.

OWS-50005
Exception while retrieving the soap message from the internal callback handler.

Category:
WebService

Cause:
Refer to the details of the message for further information on possible causes.

Action:
Refer to the details of the message for further information on possible actions.

OWS-50006
Could not deserialize the soap message to get the return value

Category:
WebService

Cause:
Refer to the details of the message for further information on possible causes.

Action:
Refer to the details of the message for further information on possible actions.

OWS-50007
Could not create the instance of asynchronous response bean of type "{0}"

Category:
WebService

Cause:
Cound not create the response Refer to the details of the message for further information on possible causes.

Action:
Check if the bean has a default constructor and the constructor is accessible.

OWS-50008
Cound not set the field "{0}" in the object of type "{1}".

Category:
WebService

Cause:
Possible causes are invalid field name, abcense of setter, inaccessible setter or mismatched field type.

Action:
Correct the bean class based on the details of the message.

OWS-50009
The method "{0}" must have a parameterized return type.

Category:
WebService

Cause:
The return type must be parameterized with the ResponseBean or the actual return type of the web service call.

Action:
Add the appropriate return type as the parameter of the AsyncHandler parameter. Or use the JAX-WS artifacts generation tools to generate the proper interface of asynchronous methods.

OWS-50010
Dispatch currently does not support REST style service.

Category:
WebService

Cause:
The AsyncHandler parameter must be parameterized with the ResponseBean or the actual return type of the web service call.

Action:
Add the appropriate return type as the parameter of the Response. Or use the JAX-WS artifacts generation tools to generate the proper interface of asynchronous methods.

OWS-50011
Dispatch currently does not support REST style service.

Category:
WebService

Cause:
The REST request cannot be processed via Dispatch. The feature is not yet supported.

Action:
Construct an HTTP Request for a RESTful webservice.

OWS-50012
Could not determine the soap version from the BindingType annotation"s value "{0}". Assuming SOAP version as 1.1

Category:
WebService

Cause:
The value of the BindingType annotation is invalid.

Action:
Use one of the valid values for the BindingType annotation. Refer to the documentation of javax.xml.ws.BindingType.

OWS-50013
Could not determine a valid protocol binding to generate for the binding public static final String {0}. A SOAP 1.1 binding will be the only protocol binding generated in the WSDL.

Category:
WebService

Cause:
The value of the BindingType is not supported or is invalid

Action:
Only SOAP and HTTP protocols are supported. Refer to the documentation or JAX-WS specification for valid values for javax.xml.ws.BindingType.

OWS-50014
Both @Deployment.restSupport() and @BindingType(javax.xml.ws.http.HTTPBinding.HTTP_BINDING) were specified. Only the latter will be used.

Category:
WebService

Cause:
Both the @Deployment.restSupport() and @BindingType(javax.xml.ws.http.HTTPBinding.HTTP_BINDING) were provided.

Action:
@Deployment.restSupport() has been deprecated. It should not be used. Use @BindingType(javax.xml.ws.http.HTTPBinding.HTTP_BINDING) instead.

OWS-50015
The given ws-addressing namespace "{0}" is not one of the supported wsa versions.

Category:
WebService

Cause:
The input ws addressing version is not supported

Action:
Correct the addressing version to use 2003/03 or 2004/08 or 2005/08.

OWS-50016
IOException converting AddressingInfo to public static final String.

Category:
WebService

Cause:
IO error converting addressing info to public static final String

Action:
correctAddressingInfo

OWS-50017
Port Metadata missing from the given callback interface class.

Category:
WebService

Cause:
Metadata such as port name or targetnamespace can not be found from the given input class.

Action:
Add the needed annotation to the interface class.

OWS-50018
The file "{0}" does not exist.

Category:
WebService

Cause:
The file name specified in syncInterfaceFileName could not be opened.

Action:
Check if the file name is correct and it exist.

OWS-50019
The file "{0}" should have some class or interface defined.

Category:
WebService

Cause:
The syncInterfaceFileName is not containing any class.

Action:
Check if the file has any class defined. Make sure that the file is compilable and so free of errors.

OWS-50020
There is no method in the file "{0}" to convert to asynchronous method.

Category:
WebService

Cause:
The interface file should have at least one method defined.

Action:
Add the required methods in the interface file.

OWS-50021
Cannot determine what methods to convert to asynchronous in file "{0}".

Category:
WebService

Cause:
The interface file has more than one method defined and no method name has been specified for conversion.

Action:
Please sepcify what methods need to be converted to asynchronous methods.

OWS-50022
The file "{0}" does not exist.

Category:
WebService

Cause:
The file name specified in asyncInterfaceFileName could not be opened.

Action:
Check if the file name is correct and it exist.

OWS-50023
The file "{0}" should have some class or interface defined.

Category:
WebService

Cause:
The asyncInterfaceFileName is not containing any class.

Action:
Check if the file has any class defined. Make sure that the file is compilable and so free of errors.

OWS-50024
Java Model is not set in the file system.

Category:
WebService

Cause:
The file system does not have any Java Model set.

Action:
Make sure that the file system has the Java Model set.

OWS-50025
JAX-WS endpoint bean has @SOAPBinding.use annotation that specifies the 'encoded' message format which is not supported in JAX-WS. JAX-WS 2.0 mandates 'literal' use only and supports either rpc/literal or document/literal style binding.

Category:
WebService

Cause:
In JAX-WS endpoint bean, @SOAPBinding.use annotation has 'encoded' value which is not supported in JAXWS

Action:
In JAX-WS endpoint bean, use either rpc/literal or document/literal style binding.

OWS-50026
Invalid use of @WebMethod annotation on method "{0}".As per JSR-181, if 'exclude' element is specified on @WebMethod annotation then other elements must not be specified with it.

Category:
WebService

Cause:
In JAX-WS endpoint bean, @WebMethod annotation has 'exclude' element that is used with other elements like 'action' or 'operationName' which is against the JSR-181 spec

Action:
Do not use 'action' or 'operationName' element if 'exclude' element is specified on @WebMethod annotation.

OWS-50027
@SOAPBinding annotation is only allowed on a method if SOAPBinding.style is "DOCUMENT". Method "{0}" specifies @SOAPBinding.style to "RPC" which is against JSR-181 so it will be ignored and default sytle "DOCUMENT/LITERAL" will be used.

Category:
WebService

Cause:
@SOAPBinding annotation at method level has 'rpc' style which is not valid as per JSR-181

Action:
Do not specify the 'rpc' style with @SOAPBinding annotation used at method level in JAX-WS enpoint interface/bean.

OWS-50028
The parameter/return type "{0}" in the method "{1}" is not supported. This method will not be exposed.

Category:
WebService

Cause:
The parameter/return type is NOT supported.

Action:
Do not use the unsupported JAVA Type in method parameter or return value.

OWS-50029
The method "{0}" has more than one input parameter that is not mapped to a header and style is BARE. This method will not be exposed.

Category:
WebService

Cause:
The java method has more than one input parameter that is not mapped to a header.

Action:
Map java parameters to a header using @WebParam annotation or use wrapped style operation.

OWS-50030
wsdlDocumentLocation is currently not supported.

Category:
WebService

Cause:
WSDLDocumentLocation is currently not supported

Action:

OWS-50031
Input address, serviceName and endpointName can not be all null

Category:
WebService

Cause:
ServiceName, PortName, or Address can not be all null.

Action:
Supply a non null argument for one of the parameters.

OWS-50032
Service name has not been specified for a non null port name.

Category:
WebService

Cause:
ServiceName can not be null when port name is specified.

Action:
Supply a non null service name.

OWS-50033
Exception occured building W3CEndpointReference.

Category:
WebService

Cause:
Exception occured when building W3C EndpintReference.

Action:
Verify that the Endpoint Reference address and other metadata to build W3C EndpointRefence are correct.

OWS-50034
The method "{0}" is ignored. {1}

Category:
WebService

Cause:
The JAVA method is ignored in WSDL generation.

Action:

OWS-50035
"{0}" cannot be used as parameter type or return value in "{1}".

Category:
WebService

Cause:
The JAVA type cannot be used as parameter type or return value in RPC-Literal and Document-Literal-BARE.

Action:

OWS-50036
Operations on portType should be unique, use @WebMethod(operationName="...") on java method "{0}" to resolve conflict.

Category:
WebService

Cause:
Operations the WSDL port type need to be unique.

Action:
Map non-unique JAVA method names to unique WSDL opeartion names using @WebParam(operation"...")

OWS-50037
Failed to load endpoint interface class "{0}" specified with @WebService.endpointInterface annotation in endpoint bean class "{1}". This may cause unexpected behavior like generated WSDL would be different from the expected one.

Category:
WebService

Cause:
Classloader failed to load the enpoint interface class that is implemented by the enpoint bean class

Action:
Check that the endpoint interface class is in the classpath

OWS-50038
Found "{0}" annotation on class "{1}" which is not allowed with PortableWebService endpoint class.

Category:
WebService

Cause:
User has specified the annotation on either webservice endpoint interface or implementation class which is not allowed with Portable WebService

Action:
Remove annotation which is not valid with @PortableWebService annotation.

OWS-50039
Could not load callback interface "{0}". Any methods defined in the interface will be ignored

Category:
WebService

Cause:
Callback interface class is not available or misspelt.

Action:
Make callback interface available.

OWS-50040
Failed while accessing Keystore details.

Category:
WebService

Cause:
Keystore details are not setup.

Action:
Configure keystore details for the server.

OWS-50042
[MessageID: {0}] Request MDB could not complete asynchronous request processing successfully. No response will be sent to the client. Analyze the details of the exception as it is likely server side configuration error.

Category:
WebService

Cause:
Asynchronous request processing resulted in exception

Action:
Analyze the exception and take appropriate action.

OWS-50043
JMS queue connection failed.

Category:
WebService

Cause:
JMS queues are not created, or wrong queue names are used.

Action:
Check that queues are created and referenced with the right names.

OWS-50044
[MessageID: {0}] Could not post async request message to the JMS queue.

Category:
WebService

Cause:
JMS queues are not created, or wrong queue names are used.

Action:
Check that queues are created and referenced with the right names

OWS-50045
Could not close the connection to JMS queue

Category:
WebService

Cause:
Internal error.

Action:
Can be ignored.

OWS-50047
[MessageID: {0}] No JMS queue specified for the request with non-anonymous replyTo for service "{1}"

Category:
WebService

Cause:
JMS queues are not created, or wrong queue names are used.

Action:
Check that queues are created and referenced with the right names

OWS-50048
ConnectionFactory for the destination "{0}" used for asynchronous service processing is not specified. Using default: "{1}"

Category:
WebService

Cause:
Connection factory is not specified.

Action:
Specify connection factory if default is not good.

OWS-50051
JMS queue for async service processing not found. Configure a JMS queue for this application.

Category:
WebService

Cause:
JMS queue are either not created or not correctly specified in the source annotations.

Action:
Verify that the JMS queues are created and the same are referred in the annotations in the service implementation class.

OWS-50056
Received a fault and user did not supply a fault listener. Details: "{0}"

Category:
WebService

Cause:
The web service implementation class does not have any methods annotated as FaultListener and either the input is fault, or the response from the callback service is fault.

Action:
Add the fault listener method if desired.

OWS-50057
Failed while re-creating the soap message from the JMS message

Category:
WebService

Cause:
System error

Action:
Analyze the exception reported in the log.

OWS-50058
Failed while re-creating the addressing header from the JMS message

Category:
WebService

Cause:
System error

Action:
Analyze the exception reported in the log.

OWS-50059
[MessageID: {0}] Error while processing the message off the JMS queue.

Category:
WebService

Cause:
System error

Action:
Analyze the exception details.

OWS-50061
Context is available locally. Should happen only while running in-process message listener.

Category:
WebService

Cause:
Internal system error.

Action:
Internal system error.

OWS-50062
[MessageID: {0}] Error while processing response. Will try the fault handler in web service implementation class.

Category:
WebService

Cause:
Callback service may be down or policy of the callback service is not matching with the callback client.

Action:
Analyze the exception details.

OWS-50064
[MessageID: {0}] Failed to send async response to client-side callback receiver.

Category:
WebService

Cause:
Callback service may be down, the callback URL may be wrong or callback service is not configured properly.

Action:
Verify the configuration of callback service and take action based on the details of exception.

OWS-50066
Could not save the context for async service in cache with the key "{0}".

Category:
WebService

Cause:
Internal system error.

Action:
Internal system error.

OWS-50067
Could not cleanup the context for async service from cache as it was not found.

Category:
WebService

Cause:
Internal system error.

Action:
Internal system error.

OWS-50069
Could not remove the saved context for async service from cache with the key "{0}".

Category:
WebService

Cause:
Internal system error

Action:
Internal system error.

OWS-50071
[MessageID: {0}] Error while trying the fault handler in web service implementation class.

Category:
WebService

Cause:
The fault handler method did not execute successfully.

Action:
Check the fault handler code.

OWS-50072
[MessageID: {0}] Got SOAPFaultException while executing the asynchronous operation

Category:
WebService

Cause:
This might be because of invalid request, missing resources in the service implementation or a bug.

Action:
Analyze the exception details.

OWS-50073
[MessageID: {0}] Encountered exception or error while invoking user's Java Web Service method.

Category:
WebService

Cause:
This might be because of invalid request, missing resources in the service implementation or a bug.

Action:
Analyze the exception or error details.

OWS-50080
[MessageID: {0}] Response MDB encountered exception during asynchronous response processing.

Category:
WebService

Cause:
Callback service is not up or it's configuration/policy is not matching with the async server.

Action:
Analyze the exception and configure the callback service.

OWS-50081
[MessageID: {0}] Response MDB encountered exception.

Category:
WebService

Cause:
Callback service is not up or it's configuration/policy is not matching with the async server.

Action:
Analyze the exception and configure the callback service.

OWS-50082
[MessageID: {0}] Response MDB will not retry sending response as callback service sent soap fault back. HTTP response code received by response MDB was "{1}".

Category:
WebService

Cause:
Callback service sent the fault back. Retrying may not help. There may be some configuration problem,

Action:
Analyze the fault and configure the client-side callback service properly.

OWS-50085
[MessageID: {0}] Could not create the user transaction for request processing.

Category:
WebService

Cause:
Internal system error.

Action:
Analyze the exception in the log.

OWS-50087
[MessageID: {0}] Could not begin the user transaction for request processing.

Category:
WebService

Cause:
Internal system error.

Action:
Analyze the exception in the log.

OWS-50088
[MessageID: {0}] Could not create user transaction for Web Method execution.

Category:
WebService

Cause:
Internal system error.

Action:
Analyze the exception in the log.

OWS-50090
[MessageID: {0}] Could not begin user transaction for Web Method execution.

Category:
WebService

Cause:
Internal system error

Action:
Analyze the exception in the log.

OWS-50092
[MessageID: {0}] Could not suspend the main transaction for executing the web method.

Category:
WebService

Cause:
Internal system error.

Action:
Internal system error.

OWS-50093
[MessageID: {0}] User transaction was marked for rollback after executing the web method.

Category:
WebService

Cause:
Web method execution marked the transaction for rollback.

Action:
It might be because of invalid input or a bug in the web method. Analyze the failure.

OWS-50094
[MessageID: {0}] Could not rollback the user transaction after executing the web method.

Category:
WebService

Cause:
Internal system error.

Action:
Analyze the exception in the log.

OWS-50095
[MessageID: {0}] User transaction is being rolledback after getting unexpected exception in executing the web method.

Category:
WebService

Cause:
Web method did not complete successfully.

Action:
It might be because of invalid input or a bug in the web method. Analyze the failure.

OWS-50096
[MessageID: {0}] User transaction is being rolled back after getting failure in getting response.

Category:
WebService

Cause:
There might be some problem with the callback service or its configuration.

Action:
Check if the callback service is up and configured properly.

OWS-50100
[MessageID: {0}] Could not get the transaction manager (javax.transaction.TransactionManager).

Category:
WebService

Cause:
Internal system error.

Action:
Internal system error.

OWS-50102
[MessageID: {0}] Could not resume the suspended main transaction.

Category:
WebService

Cause:
Internal system error

Action:
Internal system error.

OWS-50103
[MessageID: {0}] Rolled back a user transaction after executing the web method.

Category:
WebService

Cause:
There might be some problem with the callback service or its configuration.

Action:
Check if the callback service is up and configured properly.

OWS-50104
[MessageID: {0}] Could not rollback a user transaction after executing the web method.

Category:
WebService

Cause:
Internal system error.

Action:
Internal system error.

OWS-50106
[MessageID: {0}] Could not commit the user transaction for web method execution.

Category:
WebService

Cause:
Internal system error.

Action:
Analyze the related exception report in the log.

OWS-50107
[MessageID: {0}] Could not rollback the main transaction

Category:
WebService

Cause:
Internal system error.

Action:
Internal system error.

OWS-50108
[MessageID: {0}] Could not commit the main transaction

Category:
WebService

Cause:
Internal system error.

Action:
Internal system error.

OWS-50109
[MessageID: {0}] HTTP response code received from client-side callback service is "{1}".

Category:
WebService

Cause:
Callback service returned HTTP response other than 200 or 202.

Action:
Analyze the details of soap message returned by callback service or the HTTP error code.

OWS-50111
[MessageID: {0}] Received soap fault from the client-side callback service.

Category:
WebService

Cause:
Callback has sent a soap fault as the response.

Action:
Analyze the fault and configure the callback service properly.

OWS-50112
[MessageID: {0}] Could not dump the soap message

Category:
WebService

Cause:
Internal system error.

Action:
Internal system error.

OWS-50113
[MessageID: {0}] Could not create SSLSocketFactory.

Category:
WebService

Cause:
Keystore may not have been configured properly.

Action:
Configure the keystore details for the server.

OWS-50114
[MessageID: {0}] KeyStore file locations are not available. Configure it for the server to make the SSL work.

Category:
WebService

Cause:
Keystore may not have been configured properly.

Action:
Configure the keystore details for the server.

OWS-50115
Exception in handler chain

Category:
WebService

Cause:
Handler chain has thrown some exception

Action:
Look at the details of exception.

OWS-50117
Unsupported message context, jaxws handler will not be called

Category:
WebService

Cause:

Action:

OWS-50118
Unsupported message context, "{0}" could not handle fault

Category:
WebService

Cause:

Action:

OWS-50121
Error parsing handler chain: "{0}"

Category:
WebService

Cause:

Action:

OWS-50122
Could not process callback interface "{0}". Any methods defined in the interface will be ignored

Category:
WebService

Cause:

Action:

OWS-50123
Unsupported operation when generating schemas "{0}"

Category:
WebService

Cause:

Action:

OWS-50124
Unknown Exception when generating schemas: "{0}"

Category:
WebService

Cause:

Action:

OWS-50125
Could not load schema from location "{0}".

Category:
WebService

Cause:

Action:

OWS-50127
Could not determine wsdl ports.

Category:
WebService

Cause:

Action:

OWS-50128
Could not find service "{0}"; Using first service in WSDL instead.

Category:
WebService

Cause:

Action:

OWS-50129
No wsdl location or document specified

Category:
WebService

Cause:

Action:

OWS-50130
No web module with name of "{0}" so a new war will be created

Category:
WebService

Cause:
TBD

Action:
TBD

OWS-50131
Found web module with name of "{0}", so the generated contents will be merged.

Category:
WebService

Cause:
TBD

Action:
TBD

OWS-50132
Can not specify war argument and have an input be an ear that contains a war with a matching context root.

Category:
WebService

Cause:
TBD

Action:
TBD

OWS-50133
Error extracting war "{0}".

Category:
WebService

Cause:
TBD

Action:
TBD

OWS-50134
Error while processing ejb-jar.xml for ejb module at "{0}".

Category:
WebService

Cause:

Action:

OWS-50135
Could not load jaxrpc annotation parser, the webservices in this ejb will not be manageable

Category:
WebService

Cause:
TBD

Action:
TBD

OWS-50136
Multiple webservice descriptions in webservices.xml has the same port name "{0}" and service name "{1}", defaulting to webservice description named "{2}".

Category:
WebService

Cause:

Action:

OWS-50138
Could not write operation metadata for "{0}".

Category:
WebService

Cause:
Exception in writing operation metadata

Action:
Analyze the exception.

OWS-50139
HandlerChain configuration file: "{0}".

Category:
WebService

Cause:
TBD

Action:
TBD

OWS-50140
Failed to resolve HandlerChain annotation "file" value ({0}) as it is specified on "{1}"

Category:
WebService

Cause:
TBD

Action:
TBD

OWS-50141
Fabric Registration ignored because this service does not use SDO binding.

Category:
WebService

Cause:
TBD

Action:
TBD

OWS-50143
Fabric Registration ignored because Register class "{0}" can not be instantiated.

Category:
WebService

Cause:

Action:

OWS-50144
Fabric Registration ignored because Register class "{0}" can not be accessed.

Category:
WebService

Cause:

Action:

OWS-50146
Fabric Registration failed due to exception: "{0}".

Category:
WebService

Cause:

Action:

OWS-50147
SDO Type Registration failed due to exception: "{0}".

Category:
WebService

Cause:
TBD

Action:
TBD

OWS-50149
There is more than one webservice with the name of "{0}" this can cause problems at deployment or runtime. To resolve the conflict add a serviceName property to a WebService annotation

Category:
WebService

Cause:

Action:

OWS-50151
The service name "{0}" could not be found in the wsdl "{1}". Defaulting to the first service in the wsdl "{2}"

Category:
WebService

Cause:

Action:

OWS-50152
The port name "{0}" could not be found in the wsdl "{1}". Defaulting to the first port named "{2}" in the service named "{3}"

Category:
WebService

Cause:

Action:

OWS-50153
Multiple port components have the same service name "{0}" and port name "{1}", default to port component name "{2}".

Category:
WebService

Cause:

Action:

OWS-50154
Can not add partner links to wsdl because there are not two port types, actual number is "{0}".

Category:
WebService

Cause:

Action:

OWS-50155
Error processing handler chain: "{0}"

Category:
WebService

Cause:

Action:

OWS-50156
Unsupported type when generating schemas: "{0}"

Category:
WebService

Cause:

Action:

OWS-50159
[MessageID: {0}] Messages could not be read while cleaning up the asynchronous message queues. Exception: "{1}".

Category:
WebService

Cause:
System error

Action:
Internal error

OWS-50162
[MessageID: {0}] Request message was found in the queue while processing the response

Category:
WebService

Cause:
There might be a server/jvm crash after successful execution of business logic.

Action:
No action required.

OWS-50163
[MessageID: {0}] Response is not available. The web method execution did not complete or the response was lost.

Category:
WebService

Cause:
Response is not available. The web method execution did not complete or the response was lost.

Action:
Retry calling the method if it is safe to do so.

OWS-50177
Could not read saved context for async service from cache using the key: "{0}".

Category:
WebService

Cause:
Internal system error.

Action:
Internal system error.

OWS-50178
The password for the identity keystore could not be read from the security credential store while sending the response to the callback service. It should have been stored as key "{0}" in the map "{1}". Assuming no password is necessary.

Category:
WebService

Cause:
The password for the identity keystore is probably not saved in the security credentials or, the map or the key name may be wrong.

Action:
Save the password with appropriate key and the map as specified in the error.

OWS-50179
The password for recovering the key could not be read from the security credential store while sending the response to the callback service. It should have been stored as key "{0}" in the map "{1}". Assuming key password to be same as the identity keystore password.

Category:
WebService

Cause:
The password for the private key is probably not saved in the security credentials or, the map or the key name may be wrong.

Action:
Save the password with appropriate key and the map as specified in the error.

OWS-50180
The password for the trust keystore could not be read from the security credential store while sending the response to the callback service. It should have been stored as key "{0}" in the map "{1}". Assuming no password is necessary.

Category:
WebService

Cause:
The password for the trust keystore is probably not saved in the security credentials or, the map or the key name may be wrong.

Action:
Save the password with appropriate key and the map as specified in the error.

OWS-50181
Exception while accessing the password from the security credential store for using SSL while sending the response to the callback service.

Category:
WebService

Cause:
Internal system error.

Action:
Analyze the details of the exception

OWS-50183
Could not get the transaction manager using "{0}". Exception: "{1}"

Category:
WebService

Cause:
Method of getting transaction manager might have changed in this release.

Action:
Internal system error.

OWS-50184
Could not get the transaction manager using "{0}"Got unexpected class "{1}" instead of javax.transaction.TransactionManager.

Category:
WebService

Cause:
Method of getting transaction manager might have changed in this release.

Action:
Internal system error.

OWS-50187
[MessageID: {0}] System Error: Could not get the addressing namespace and so the None URI.

Category:
WebService

Cause:
Addressing namespace is not available.

Action:
Internal system error.

OWS-50198
The content negotiation strategy {0} is incompatible with a service that has FastInfoset disabled according to the WSDL

Category:
WebService

Cause:
The content negotiation strategy provided is incompatible with a Service that has FastInfoset Disabled

Action:
Do not supply a content negotiation strategy On the client

OWS-50199
The FastInfoset content negotiation strategy '{0}' specified in the request context property conflicts with the value '{1}' specified on the feature object

Category:
WebService

Cause:
The content negotiation request context property provided conflicts with the content negotiation feature set on the same client

Action:
Supply either a content negotiation request context property or a feature, not both. If both are provided, make sure they are set to the same value

OWS-50200
The FastInfosetFeature provided on the client has enabled = {0}, while the service WSDL has enabled = {1}. The client value will override the value read from the WSDL

Category:
WebService

Cause:
The FastInfosetFeature provided on the client is different from that advertised on the service WSDL - client feature will be used as an override

Action:
Make sure that the intent was to override the value advertised in the service WSDL - if not, remove the feature on the client

OWS-50201
Found invalid policy references on WebService endpoint. Please make sure you do not have mulitple or conflicting policy refrerences on your webservice endpoint.

Category:
WebService

Cause:
There is invalid policy set due to conflicting or multiple policy references of same category on given JAXWS endpoint.

Action:
Make sure that there are no multiple or conflicting policy refeences specified on webservcie endpoint.

OWS-50205
Could not create request and response JMSChannel instances required to post JMS messages.

Category:
WebService

Cause:
Internal system error

Action:
Analyze the details of the exception

OWS-50207
Could not open the jar in specified path "{0}"

Category:
WebService

Cause:
The jar is not in the path or the jar format error has occurred

Action:
Check if the jar is in the path or with a wrong path in the Manifest file of current ejb jar which depends on it, then check if the jar has broken

OWS-51001
No TypeGeneratorFactory implementation found for factory {0}.

Category:
WebService

Cause:
You may have specified a wrong factory name, or your Web Service libraries are not properly configured.

Action:
Please ensure that you have specified a valid factory name.

OWS-51500
Unable to open or locate the following file or directory: {0}.

Category:
WebService

Cause:
A file or directory was not found or acessible.

Action:
Ensure that the file or directory name is properly specified and accessible.

OWS-51501
No schema mapping found for class {0}

Category:
WebService

Cause:

Action:

OWS-60002
Could not resolve schema resource for namespace "{0}" at location "{1}"

Category:
WebService

Cause:
Could not resolve the schema from given schemaLocation. This may be caused by network problem or malformed or incorrect schemaLocation URL/URI

Action:

OWS-60003
Serializer initialization failed. Unable to define SDO data types.

Category:
WebService

Cause:
Failed to define SDO data types from the given schema/schemas.

Action:
Ensure that the schema/schemas provided through schemaLocation is/are valid and none of the schemas are conflicting with each other.

26

PKI-01001 to PKI-07023

PKI-01001
Missing arguments in the command: {0}

Category:
Other

Cause:
An incomplete command was issued. For example, the wallet password or wallet location is missing.

Action:
Check the usage of the command-line tool and provide all required arguments.

PKI-01002
Invalid password.

Category:
Other

Cause:
Passwords must have a minimum length of eight characters and contain alphabetic characters combined with numbers or special characters.

Action:
Make sure the password policy is followed and try again.

PKI-01003
Passwords did not match.

Category:
Other

Cause:
When creating a wallet, the password entered the second time did not match the password entered the first time.

Action:
Enter the same password both times.

PKI-01004
Cannot specify both keysize and ecccurve options. Please specify keysize for RSA keys, and ecccurve for ECC keys.

Category:
Other

Cause:
Cannot specify both keysize and ecccurve options. Please specify keysize for RSA keys, and ecccurve for ECC keys.

Action:
Specify only one option either keysize or ecccurve

PKI-02001
A wallet already exists at: {0}

Category:
Other

Cause:
Attempted to create a new wallet at a location where a wallet already existed.

Action:
Remove the existing wallet, or create the new wallet at another location.

PKI-02002
Unable to open the wallet. Check password.

Category:
Other

Cause:
Wallet password may be wrong.

Action:
Try again with the correct password.

PKI-02003
Unable to load the wallet at: {0}

Category:
Other

Cause:
Possible causes include a wrong password, parsing errors, or the wallet file was not found.

Action:
Check that the wallet is present at the specified location and the password is correct.

PKI-02004
Unable to verify the wallet.

Category:
Other

Cause:
The wallet may be corrupted.

Action:
Make sure you have the right wallet. Try opening the wallet in enterprise manager or by orapki to make sure it is appropriate.

PKI-02005
Unable to delete the wallet at: {0}

Category:
Other

Cause:
Possible causes include insufficient permission or the wallet being used by another person.

Action:
Obtain the necessary permission and check that the wallet is not being used.

PKI-02006
The specified directory does not exist: {0}

Category:
Other

Cause:
Wallet creation failed because the specified directory did not exist.

Action:
Create the directory prior to the wallet creation.

PKI-02007
The specified location is not a directory: {0}

Category:
Other

Cause:
Wallet creation failed because the specified location was not a directory.

Action:
Create the wallet in an existing directory instead.

PKI-02008
Unable to modify a read-only Auto-login wallet.

Category:
Other

Cause:
Attempted to update a read-only Auto-login wallet.

Action:
Specify the associated Password-protected (.p12 file) wallet.

PKI-02009
Unable to create directory.

Category:
Other

Cause:
OS error in creating directory.

Action:
Check file permissions and disk space.

PKI-02010
Invalid MAC for Wallet. Wallet verification failed.

Category:
Other

Cause:
The wallet is possibly corrupted.

Action:
Restore the wallet from a backup or recreate it.

PKI-02011
Unable to set file permissions for wallet at {0}

Category:
Other

Cause:
Wallet permissions could not be set.

Action:
Try to save the wallet in a different directory.

PKI-02012
Unable to lock file at

Category:
Other

Cause:
May be file channel get closed or blocked while getting lock on p12 or sso file in wallet.

Action:
Try to achieve lock again on wallet.

PKI-02013
Unable to create/parse RSA credentials.

Category:
Other

Cause:
RSA algorithm to create key pair is missing.

Action:
A JCE implementation that supports RSA is required.

PKI-02014
Unable to create/parse ECC credentials.

Category:
Other

Cause:
ECC algorithm to create key pair is missing.

Action:
A JCE implementation that supports ECC is required.

PKI-02015
Trust Flags are not enabled for the wallet.

Category:
Other

Cause:
Trust flags are getting assigned to certificates but the wallet containing them are not permitted to have trust flags.

Action:
Wallet should be trust flag enabled before assigning trust flags to the certificates.

PKI-02016
Trust Flags are already enabled for the wallet.

Category:
Other

Cause:
Trying to enable wallet for trust flag but it is already enabled.

Action:
Wallet is already permitted for trust flags.Do not try to enable it again.

PKI-02017
Thread %d attempted to release non-existent lock

Category:
Other

Cause:
Lock does not exist.

Action:
Please check the existence of lock before releasing it.

PKI-02018
PKCS12 file does not exist.

Category:
Other

Cause:
PKCS12 file path is not valid or empty in given parameters while importing pkcs12 file.

Action:
PKCS12 file path should be valid before importing it.

PKI-03001
The entry already exists: {0}

Category:
Other

Cause:
Attempted to create a new entry with a previously used alias.

Action:
Try again with another alias or delete the existing entry.

PKI-03002
No entry found for the alias: {0}

Category:
Other

Cause:
The specified alias was not found in the secret store.

Action:
Check the alias name and try again.

PKI-03003
Secrets did not match.

Category:
Other

Cause:
The secret (password) entered the second time did not match the one entered the first time.

Action:
Enter the same secret both times.

PKI-03004
Unable to load the secret store.

Category:
Other

Cause:
Possible causes include a wrong password, the secret store file was not found or was corrupted.

Action:
Check that the secret store file is present at the specified location and the password is correct.

PKI-03005
Unable to load the Java keystore.

Category:
Other

Cause:
Possible causes include a wrong password, the Java keystore file was not found or was corrupted

Action:
Check that the Java keystore file is present at the specified location and the password is correct.

PKI-03006
An entry already exists for map {0} and key {1}

Category:
Other

Cause:
Credentials already exist in Secret store.

Action:
Different username and password to be used to store credentials in secret store.

PKI-03007
An entry does not exist for map {0} and key {1}

Category:
Other

Cause:
Credentials do not exist in Secret store.

Action:
Credentials need to be stored before modification can be done on them.

PKI-03008
The specified credential map name is invalid

Category:
Other

Cause:
Map name given is not valid.

Action:
Map name should be valid.

PKI-03009
The specified credential key name is invalid

Category:
Other

Cause:
Key name is not valid or present.

Action:
Key name should be valid.

PKI-04001
Invalid Certificate.

Category:
Other

Cause:
The given certificate did not follow the X509/DER, X509/BASE64, PKCS7/DER, or PKCS7/BASE64 format.

Action:
Use a valid certificate format.

PKI-04002
No valid key or certificate in the wallet.

Category:
Other

Cause:
Attempted to use a wallet for authentication/signatures/SSL, but no key or certificate was found in the wallet.

Action:
Import certificates into the wallet/keystore or use a self-signed wallet/keystore.

PKI-04003
The trusted certificate is already present in the wallet.

Category:
Other

Cause:
Attempted to import a trusted certificate that already existed in the wallet.

Action:
No action required. The trusted certificate is already present in the wallet.

PKI-04004
The user certificate is already installed in the wallet.

Category:
Other

Cause:
Attempted to install a user certificate that already existed in the wallet.

Action:
No action required. The user certificate is already installed in the wallet.

PKI-04005
No matching certificate request in the wallet.

Category:
Other

Cause:
Attempted to install a user certificate, but no matching certificate request was found in the wallet.

Action:
Make sure that the user certificate is being installed into the wallet where the certificate request was created.

PKI-04006
No matching private key in the wallet.

Category:
Other

Cause:
Attempted to install a user certificate, but no matching private key was found in the wallet.

Action:
Make sure that the user certificate is being installed to the wallet where the certificate request was created.

PKI-04007
No matching certificate in the wallet for the DN: {0}

Category:
Other

Cause:
Attempted to access a user certificate, but no matching certificate of the DN was found.

Action:
Make sure that a user certificate with the given DN exists in the wallet.

PKI-04008
An entry with the specified alias already exists in the wallet: {0}

Category:
Other

Cause:
Attempted to create a key or import a certificate with an alias, but the alias already existed in the wallet.

Action:
Try again with another alias.

PKI-04009
No matching private key or certificate request found for the alias: {0}

Category:
Other

Cause:
Attempted to install a user certificate into a wallet with an alias, but no matching private key / certificate request was found for this alias.

Action:
Make sure that the user certificate is being installed with the same alias as the private key / certificate request.

PKI-04010
No matching certificate found for the alias: {0}

Category:
Other

Cause:
Attempted to access a user certificate that is associated with an alias, but no matching certificate was found for this alias.

Action:
Make sure that a user certificate exists in the wallet with the given alias.

PKI-04011
Cannot remove the certificate request if its associated user certificate is still present in the wallet.

Category:
Other

Cause:
Attempted to remove a certificate request, but its associated user certificate was still present in the wallet.

Action:
Remove the associated user certificate first.

PKI-04012
Incomplete certificate chain

Category:
Other

Cause:
Attempted to install a user certificate whose trusted certificate was not present in the wallet.

Action:
Ensure that the CA certificate/Certificate Chain that issued the user certificate is present as trusted certificate in the wallet.

PKI-04013
Entry with matching alias not trusted cert.

Category:
Other

Cause:
Failed to add a trusted certificate into the wallet because the entry with that alias in the keystore was not a trusted cert.

Action:
Specify a different alias.

PKI-04014
No entry with matching alias is present in wallet/keystore.

Category:
Other

Cause:
Failed to delete an entry in wallet/keystore because no entry with that alias was present.

Action:
Specify the correct alias.

PKI-04015
Trusted cert cannot be removed.

Category:
Other

Cause:
The trusted cert is being used in a certificate chain.

Action:
The user cert that has the trusted cert in its certificate chain should be removed first.

PKI-04016
No user certificate found in the wallet.

Category:
Other

Cause:
No user certificate that can be used with SSL was found.

Action:
Install a user certificate into the wallet.

PKI-04017
Entry identified by alias is not a key entry.

Category:
Other

Cause:
No entry in wallet/keystore had matching alias.

Action:
Use a correct alias.

PKI-04018
User cert does not match private key for input alias.

Category:
Other

Cause:
The private key with matching alias did not match the user certificate.

Action:
Use a correct alias.

PKI-04019
Certificate uses unsupported Public Key Algorithm %s.

Category:
Other

Cause:
Key algorithm used is different than RSA or ECC.

Action:
RSA and ECC are only supported

PKI-04020
The certificate already exists in the given path

Category:
Other

Cause:
Certificate already exists at given path.

Action:
Path should be valid to create a new certificate.

PKI-04021
Invalid value(s) of Trust Flags provided.

Category:
Other

Cause:
Trust flag value(s) provided is/are not according to given ones.

Action:
Trust Flags value should be valid one.

PKI-04022
Invalid value of Serial Number provided.

Category:
Other

Cause:
Serial number is not valid. It does not consist of numeric value

Action:
Serial number should be valid.

PKI-04023
No Matching certificate found for given input parameters.

Category:
Other

Cause:
No certificate is found for given subject.

Action:
Subject should be valid of a existing certificate.

PKI-04024
Cannot assign Trust Flags while importing a certificate chain.

Category:
Other

Cause:
Same Trust flag is getting assigned to all certificates in chain.

Action:
All certificates in chain cannot be assigned same trust flag .Correct trust flags need to be assigned.

PKI-04025
Unique certificate cannot be identified.

Category:
Other

Cause:
Multiple certificates with matching parameters exist.

Action:
There should be single certificate of matching subject to do modifications on it

PKI-04026
Certificate of cert or CRL's signer has expired.

Category:
Other

Cause:
Certificate has been expired.

Action:
Certificate should be valid before getting added to CRL.

PKI-05001
Unable to read CRL at: {0}

Category:
Other

Cause:
CRL was not present at the specified location or CRL was corrupted.

Action:
Check the CRL file at the given location.

PKI-05002
Unable to write CRL

Category:
Other

Cause:
Insufficient file permission or insufficient disk space.

Action:
Ensure that a file can be created at the specified location.

PKI-05003
Untrusted or expired CRL

Category:
Other

Cause:
The CRL at the user-given location expired or was not signed by a trusted authority.

Action:
Get a valid or recent CRL from the CA.

PKI-05004
No CRL found for the issuer: {0}

Category:
Other

Cause:
No CRL issued by the CA was found at the specified CRL location.

Action:
Import the specified CA's CRL into the specified location.

PKI-05005
CRL symlink failed with the error: {0}

Category:
Other

Cause:
Failed to set up a symlink for the CRL file.

Action:
Make sure that the target CRL file exists and try again.

PKI-05006
Unable to find signer for CRL.

Category:
Other

Cause:
No CA certificate in wallet for the CRL issuer was found.

Action:
Add CA certificates from CRL issuer to wallet.

PKI-05007
Given CRL already Exists.

Category:
Other

Cause:
CRL is already present at given path

Action:
Valid CRL path should be given to create.

PKI-07001
Unable to login to the LDAP server.

Category:
Other

Cause:
The username or password may be invalid.

Action:
Try again with the correct credentials.

PKI-07002
Unable to find the LDAP subtree: {0}

Category:
Other

Cause:
Attempted to search for CRLs from an LDAP server, but the subtree was not found.

Action:
Confirm that the CRL file is present at the specified location.

PKI-07003
Insufficient privilege to perform the operation in the LDAP server: {0}

Category:
Other

Cause:
Attempted to perform some operation in the LDAP server for which the user did not have permission.

Action:
Obtain the necessary authorization or have an authorized user perform the operation.

PKI-07004
Peer sent no certificates.

Category:
Other

Cause:
The peer sent no certificates (which was needed during handshake).

Action:
Check peer configuration.

PKI-07005
Untrusted certificate chain.

Category:
Other

Cause:
No trusted certificate in wallet/keystore for peer certificate was found.

Action:
Peer should use a different certificate or import the peer's CA certificate into your wallet.

PKI-07006
Invalid certificate signature.

Category:
Other

Cause:
Certificate signature check failed.

Action:
Use a different user certificate/certificate chain on peer.

PKI-07007
Certificate is revoked.

Category:
Other

Cause:
The peer's certificate has been revoked.

Action:
Use a different user certificate/certificate chain on peer.

PKI-07008
Keysize must be 512 or 768 or 1024 or 2048 or 4096.

Category:
Other

Cause:
Keysize value given for certificate is not from recommended ones.

Action:
Keysize value for RSA should be either 512 or 768 or 1024 or 2048 or 4096.

PKI-07009
The elliptic curve name must be one of the fifteen NIST recommended ones.

Category:
Other

Cause:
elliptic curve values given for certificate is not from supported ones.

Action:
Elliptic curve values should be one of recommended ones.

PKI-07010
A key size must be specified when creating an RSA key.

Category:
Other

Cause:
Keysize value has not been provided for RSA key algorithm.

Action:
Keysize value is required for RSA key algorithm

PKI-07011
A curve name must be specified when creating an EC key.

Category:
Other

Cause:
Curve name is missing for ECC key algorithm.

Action:
Curve name should be provided for ECC key algorithm

PKI-07012
Unable to migrate to jks.Trust store password is null.

Category:
Other

Cause:
Trust store password is missing.

Action:
Trust store password is required during jks migration.

PKI-07013
Unable to migrate to jks.Key store password or location is null.

Category:
Other

Cause:
Key store password or location is missing while migrating jks.

Action:
Key store password and location are required.

PKI-07014
Unable to import private key.

Category:
Other

Cause:
Error occurred while importing private key to the wallet.

Action:
Importing private key is not successful.

PKI-07015
Unable to import private key.

Category:
Other

Cause:
Certificate is missing of which private key needs to be imported.

Action:
Certificate is required.

PKI-07016
Unable to export private key.

Category:
Other

Cause:
Private key is not present in wallet for this alias.

Action:
Alias should be valid.

PKI-07018
Operation is unsuccessful. Alias is missing.

Category:
Other

Cause:
Alias is missing in given parameters to search certificate

Action:
Alias is required.

PKI-07019
Unable to export certificate chain

Category:
Other

Cause:
File to which certificate chain needs to be exported is not present.

Action:
File path should be present and be valid.

PKI-07019
Unable to export certificate chain.Certificate chain file is not present.

Category:
Other

Cause:
File to which certificate chain needs to be exported is not present.

Action:
File path should be present and be valid.

PKI-07020
Unable to export certificate chain. Certificate chain is not present in wallet.

Category:
Other

Cause:
Given parameters do not match with any certificate in wallet.

Action:
All input parameters to detect certificate chain should be valid and present.

PKI-07021
Keysize cannot be null or empty.

Category:
Other

Cause:
Keysize would be either null or empty.

Action:
Keysize is required.

PKI-07022
Keysize or serial number cannot be null or empty.

Category:
Other

Cause:
Keysize or serial number would be either null or empty.

Action:
keysize and serial number are required.

PKI-07023
Wallet file has no write permission

Category:
Other

Cause:
Wallet file has no write permission.

Action:
Any modificatin in wallet file requires write permission.

27
RCU-06000 to RCU-07006

RCU-06000
Unable to connect to the database.

Category:
Repository Configuration

Cause:
Could not connect to the database. Required database connection field(s) "{0}" is/are empty.

Action:
Enter valid value in all required field(s).

RCU-06001
Port number validation failed.

Category:
Repository Configuration

Cause:
An invalid port number {0} was specified. A valid port number ranges from 1 to 65535.

Action:
Enter a valid port number.

RCU-06002
Prerequisite validation failed.

Category:
Repository Configuration

Cause:
The minimum requirements to load metadata repository were not met for the specified database.

Action:
Modify the database configuration to meet the prerequisite requirements.

RCU-06003
No metadata repository schema can be dropped.

Category:
Repository Configuration

Cause:
RCU could not find the Schema Version Registry in the database.

Action:
Contact the system administrator.

RCU-06004
Empty database user password.

Category:
Repository Configuration

Cause:
Password for the SYS database user not specified.

Action:
Enter the password for the SYS user.

RCU-06005
Unable to execute sql query.

Category:
Repository Configuration

Cause:
Database not in open state.

Action:
Make sure that the database is open.

RCU-06006
Could not identify valid Oracle Home(s).

Category:
Repository Configuration

Cause:
The inventory associated with the Oracle Home {0} does not recognize any Oracle Home(s).

Action:
Contact the system administrator to fix the issue.

RCU-06007
Error in populating database details.

Category:
Repository Configuration

Cause:
Exception "{0}" occurred while querying database.

Action:
Refer to the RCU log for details.

RCU-06011
Prefix validation failed.

Category:
Repository Configuration

Cause:
An invalid prefix was specified. A valid prefix can contain only alpha-numeric characters. It should not start with a number and should not contain any special characters.

Action:
Select a prefix from the existing prefixes or enter a new prefix.

RCU-06012
Unable to find any prefix.

Category:
Repository Configuration

Cause:
There were no existing prefixes in the Schema Version Registry of the specified database.

Action:
Refer to the rcu logs or contact the system administrator.

RCU-06013
Prefix validation failed.

Category:
Repository Configuration

Cause:
Specified prefix could not be found. Existing prefixes are: {0}

Action:
Specify a valid prefix from the existing prefix list.

RCU-06014
invalid component

Category:
Repository Configuration

Cause:
Specified component did not exist.

Action:
Provide a component that exists.

RCU-06015
Component validation failed.

Category:
Repository Configuration

Cause:
No component was selected or specified.

Action:
Select or specify at least one component.

RCU-06016
Invalid prefix specified.

Category:
Repository Configuration

Cause:
The specified prefix already exists.

Action:
Specify another prefix.

RCU-06017
Valid component is not specified.

Category:
Repository Configuration

Cause:
There was no prefix specified and the specified component already exists.

Action:
If the component is non-prefixable, only one instance can exist. To re-create the instance, drop it first and then create it again.

RCU-06018
Schema owner validation failed.

Category:
Repository Configuration

Cause:
Value for schema owner {0} was not provided.

Action:
Provide values for all schema owners.

RCU-06019
Invalid format was provided for schema owner {0}.

Category:
Repository Configuration

Cause:
Prefixable components should have the schema owner in the following format <prefix>_<Any String> where the prefix is {1}.

Action:
Ensure that the schema owners of all prefixable components begin with the prefix, followed by "_".

RCU-06020
Invalid schema owner {0}.

Category:
Repository Configuration

Cause:
Schema owner {0} was duplicated. Schema owners must be unique.

Action:
Provide unique schema owners.

RCU-06021
Existing components cannot be specified.

Category:
Repository Configuration

Cause:
The specified component ({0}) was non-prefixable, and it already exists.

Action:
Deselect the non-prefixable component as it already exists.

RCU-06022
RCU cannot be executed in resume mode.

Category:
Repository Configuration

Cause:
No components to resume execution.

Action:
Run RCU without resume option.

RCU-06030
Tablespace {0} validation for component {1} failed.

Category:
Repository Configuration

Cause:
The specified tablespace {0} for component {1} did not have enough free space to hold the repository. The required free space is {2} MB, but the available space was {3} MB.

Action:
Modify the properties of the tablespace or change the prerequisite value.

RCU-06051
RCUCommandLine Error - command line options validation failed.

Category:
Repository Configuration

Cause:
Invalid option specified.

Action:
Provide valid command line options. Remove the invalid option:

RCU-06052
RCUCommandLine Error - Error while validating command line arguments.

Category:
Repository Configuration

Cause:
Invalid format/order of command line options and values.

Action:
Ensure that the format/order of the options and values in the command line are correct.

RCU-06053
RCUCommandLine Error - command line option validation failed.

Category:
Repository Configuration

Cause:
More than one mutually exclusive option passed.

Action:
Provide valid command line options. Provide only one valid option from this list:

RCU-06054
RCUCommandLine Error - Database type validation failed.

Category:
Repository Configuration

Cause:
Database type was not provided.

Action:
Provide the database type.

RCU-06055
RCUCommandLine Error - command line arguments validation failed.

Category:
Repository Configuration

Cause:
Database connect string was not provided.

Action:
Provide the database connect string.

RCU-06056
RCUCommandLine Error - Database host name validation failed.

Category:
Repository Configuration

Cause:
Database host name was not provided.

Action:
Provide the database host name.

RCU-06057
RCUCommandLine Error - Database port number validation failed.

Category:
Repository Configuration

Cause:
Database port number was not provided.

Action:
Provide the database port number.

RCU-06058
RCUCommandLine Error - Database service name validation failed.

Category:
Repository Configuration

Cause:
Database service name was not provided.

Action:
Provide the database service name.

RCU-06059
RCUCommandLine Error - Database user validation failed.

Category:
Repository Configuration

Cause:
Database user was not provided.

Action:
Provide the database user.

RCU-06060
RCUCommandLine Error - Database password validation failed.

Category:
Repository Configuration

Cause:
Database password was not provided.

Action:
Provide the database password.

RCU-06061
RCUCommandLine Error - Database role validation failed.

Category:
Repository Configuration

Cause:
Database role was not provided.

Action:
Provide the database role.

RCU-06062
RCUCommandLine Error - Schema prefix validation failed.

Category:
Repository Configuration

Cause:
Schema prefix was not provided.

Action:
Provide the schema prefix.

RCU-06063
RCUCommandLine Error - Tablespace name validation failed.

Category:
Repository Configuration

Cause:
Tablespace name is not provided. Pass DEFAULT_VALUE to use default tablespace name.

Action:
Provide the tablespace name.

RCU-06064
RCUCommandLine Error - Schema owner name validation failed.

Category:
Repository Configuration

Cause:
Schema owner name is not provided. Pass DEFAULT_VALUE to use default schema owner name.

Action:
Provide the schema owner.

RCU-06065
RCUCommandLine Error - component name validation failed.

Category:
Repository Configuration

Cause:
Invalid component name(s) were provided : {0}

Action:
Provide valid component name(s). Supported component names can be obtained by running "-listComponents" command.

RCU-06066
RCUCommandLine Error - Error occurred while validating Checkpoint object.

Category:
Repository Configuration

Cause:
Checkpoint object was not found or was not readable. Cannot proceed in resume mode.

Action:
Refer to the RCU log and make sure that checkpoint object exists to continue in resume mode.

RCU-06067
RCUCommandLine Error - checkpoint validation failed.

Category:
Repository Configuration

Cause:
No pending components found in checkpoint. Cannot proceed in resume mode.

Action:
Invoke RCU without resume option.

RCU-06068
Checkpoint object cannot be created.

Category:
Repository Configuration

Cause:
Failed to write checkpoint object.

Action:
Refer to the RCU log for details.

RCU-06080
Global prerequisite check failed for the specified database.

Category:
Repository Configuration

Cause:
Global prerequisite check failed. Check requirement for the specified database.

Action:
Modify the database configuration to meet the global prerequisite requirements.

RCU-06081
Internal Error - unable to run prereq query in the specified database.

Category:
Repository Configuration

Cause:
Unable to obtain properties of the specified database.

Action:
Make sure that the database is in a proper state.

RCU-06082
Tablespace prerequisite check failed for the selected component.

Category:
Repository Configuration

Cause:
Tablespace prerequisite check failed. Check tablespace requirement for each selected component.

Action:
Modify the properties of the tablespace or change the prerequisite value.

RCU-06083

Category:
Repository Configuration

Cause:
Prerequisite check failed for selected component.

Action:
Refer to the RCU logs for additional details. Make sure that the prerequisite requirements are met.

RCU-06084
{0} failed.

Category:
Repository Configuration

Cause:
invalid format for Java prerequisite: {0}

Action:
Make sure that the java prerequisite is in a valid format.

RCU-06085
Java prerequisite is not met.

Category:
Repository Configuration

Cause:
Error occurred while executing Java prerequisite: {0}

Action:
Make sure that the java prerequisite is in a valid format and all required classes and jar files are present.

RCU-06086
Global prerequisite check failed.

Category:
Repository Configuration

Cause:
Schema metadata initialization failed.

Action:
Refer to RCU logs for more details.

RCU-06090
Connection step validation failed.

Category:
Repository Configuration

Cause:
Skipping main operation: failed to connect to database because database details were missing or invalid.

Action:
Provide correct database details and try again.

RCU-06091
Component validation failed.

Category:
Repository Configuration

Cause:
One or more component specific validation failed.

Action:
Check log for more details and fix the validation error.

RCU-06092
Components are not selected properly.

Category:
Repository Configuration

Cause:
Component Selection validation failed. Refer to log at {0} for details.

Action:
Select one or more components to continue.

RCU-06093
Skipping main operation because of validation error.

Category:
Repository Configuration

Cause:
Failed to validate schema tablespace.

Action:
Check the properties of the database and the tablespaces specified.

RCU-06100
Prerequisite check failed.

Category:
Repository Configuration

Cause:
Exception while executing prerequisite {0}.

Action:
Refer to the logs for details.

RCU-06101
The database prerequisite check failed for {0}

Category:
Repository Configuration

Cause:
Prerequisite failed for {0}. Current Value is {2}. It should {3} {1}

Action:
Modify database configuration to meet the prerequisite requirement.

RCU-06102
The database prerequisite check failed for {0}.

Category:
Repository Configuration

Cause:
The prerequisite {0} returned an empty result.

Action:
Modify the database configuration to meet the prerequisite requirements.

RCU-06103
The database option prerequisite check failed.

Category:
Repository Configuration

Cause:
The database option prerequisite check failed for: {0} Required Value = {1}, Current Value = {2}

Action:
Make sure that the database option has the required value.

RCU-06104
The database object prerequisite check failed.

Category:
Repository Configuration

Cause:
The database object prerequisite check fails for: {0} This object does not exist or its status is not valid.

Action:
Make sure that the database object exists and is valid.

RCU-06105
The database component prerequisite check failed.

Category:
Repository Configuration

Cause:
The database component prerequisite check failed for {0}. This component does not exist or its status is not valid.

Action:
Make sure that the database component exists and is valid.

RCU-06106
The database version prerequisite failed.

Category:
Repository Configuration

Cause:
The database version prerequisite failed because the current database version is not supported with RCU. Current Version is {1}. It should be {2} {0}.

Action:
Make sure that the database version being used is supported with RCU.

RCU-06107
The database initialization parameter prerequisite check failed.

Category:
Repository Configuration

Cause:
The database initialization parameter prerequisite check failed for {0}. Current Value is {2}. It should {3} {1}.

Action:
Make sure that the database initialization parameter has the required value.

RCU-06108
The database tablespace free space prerequisite check failed.

Category:
Repository Configuration

Cause:
The database tablespace free space prerequisite check failed for {0}. Current space is {2}. It should be {3} {1}.

Action:
Modify the properties of the tablespace or change the prerequisite value.

RCU-06120
Component dependencies check failed.

Category:
Repository Configuration

Cause:
Component dependencies not met for components with following ids: {0}.

Action:
Select the dependent components and try again.

RCU-06121
Component dependencies check failed.

Category:
Repository Configuration

Cause:
Required dependent components were not selected.

Action:
Select the dependent components and try again.

RCU-06130
Action failed

Category:
Repository Configuration

Cause:
Action failed - {0}.

Action:
Check the actions for the component or contact the system administrator.

RCU-06131
Error while connecting to the database.

Category:
Repository Configuration

Cause:
An error occurred while connecting to the database.

Action:
Provide correct database details and try again, or contact the system administrator.

RCU-06132
The database type of the specified database is not supported - {0}

Category:
Repository Configuration

Cause:
The database type of the specified database was not supported.

Action:
Use a database type that is supported.

RCU-06133
Error while executing host command action.

Category:
Repository Configuration

Cause:
An error occurred while trying to execute host command action.

Action:
Check the host command action for the component or contact the system administrator.

RCU-06134
Error while executing JDBC action.

Category:
Repository Configuration

Cause:
An error occurred while trying to execute JDBC action.

Action:
Check the jdbc action for the component or contact the system administrator.

RCU-06135
Error while executing Java action.

Category:
Repository Configuration

Cause:
An error occurred while trying to execute Java action.

Action:
Check the java action for the component or contact the system administrator.

RCU-06136
Error while executing SQLPlus action.

Category:
Repository Configuration

Cause:
An error occurred while trying to execute SQLPlus action.

Action:
Check the sqlplus action for the component or contact the system administrator.

RCU-06138
The operation has been halted.

Category:
Repository Configuration

Cause:
The operation was halted.

Action:
Click continue or restart the operation.

RCU-06139
Invalid consolidated schema name {0}.

Category:
Repository Configuration

Cause:
Consolidated schema {0} exists in database, but schema version registry table did not have an entry for the schema with expected status. The consolidated schema should be created through RCU.

Action:
Provide valid consolidated schema name.

RCU-06140
Invalid schemas to be consolidated.

Category:
Repository Configuration

Cause:
{0} was not a valid schema in the given database.

Action:
Provide valid schema name for consolidation.

RCU-06141
Schema validation failed.

Category:
Repository Configuration

Cause:
{0} cannot be consolidated.

Action:
Refer logs for details.

RCU-06142
Provided schema cannot be consolidated.

Category:
Repository Configuration

Cause:
Validation of consolidate schema failed.

Action:
Check the logs for details.

RCU-06143
Provided schema name is not a valid consolidated schema.

Category:
Repository Configuration

Cause:
Provided schema exists in database, but the schema was not valid for given consolidate operation.

Action:
Make sure schema is of type "CONSOLIDATED".

RCU-06144
Same component type schemas are provided for consolidation.

Category:
Repository Configuration

Cause:
Both schemas {0} and {1} are of type {2}. Schemas of same type cannot be consolidated.

Action:
Make sure that schemas to be consolidated are not of the same component.

RCU-06146
Invalid consolidated schema name.

Category:
Repository Configuration

Cause:
{0} was not a valid schema in the provided database.

Action:
Make sure the scripts generated during consolidateGrant are executed.

RCU-06147
Invalid command line option specified.

Category:
Repository Configuration

Cause:
Consolidate operations are supported only in silent mode.

Action:
Invoke the command with "-silent" option.

RCU-06148
Consolidated schema validation failed.

Category:
Repository Configuration

Cause:
Consolidation of an existing schema is not allowed. {0} already consolidated to the schemas {1}.

Action:
Execute "dropConsolidatedSchema" to delete the existing schema and recreate it using "consolidate". To recreate the synonyms to the existing schemas use "-reconsolidate" option.

RCU-06149
Consolidate schema validation failed.

Category:
Repository Configuration

Cause:
Failed to find consolidated schema definition for {0}. Cannot execute reconsolidate on this schema.

Action:
Refer to RCU logs for any errors.

RCU-06150
Consolidate schema validation failed.

Category:
Repository Configuration

Cause:
Specified schema {0} already exists in the database.

Action:
Drop the existing schema or generate the script using different schema name.

RCU-06151
Consolidate schema validation failed.

Category:
Repository Configuration

Cause:
Specified schema {0} does not exist in the database. Could not execute "reconsolidate" option.

Action:
Use "consolidate" option to create the consolidated schema.

RCU-06152
Consolidate schema name validation failed.

Category:
Repository Configuration

Cause:
Specified schema name "{0}" length exceeds allowed number of characters. Maximum number of characters allowed in consolidated schema name is 25.

Action:
Specify valid value for consolidated schema name.

RCU-06153
Edition value of {0} is empty.

Category:
Repository Configuration

Cause:
Specified database type is EBR. But the schema to be consolidated "{0}" is not created with this edition, "{1}". Schemas to be consolidated have to be created in the same edition as the value specified for consolidate schema.

Action:
Ensure that the schemas to be consolidated exist in the same edition as that of the consolidated schema.

RCU-06154
Specified edition/schema name is invalid.

Category:
Repository Configuration

Cause:
Schemas to be consolidated have to be created in the same edition as the value specified for consolidate schema. "{0}" schema is created with edition "{1}". But the edition specified for consolidate schema is "{2}"

Action:
Ensure that the schemas to be consolidated exist in the same edition as that of the consolidated schema.

RCU-06155
Invalid database type or schemas to be consolidated.

Category:
Repository Configuration

Cause:
Specified database type is ORACLE. Consolidated schema could not be created using schemas created in EBR database type. "{0}" schema is created with EBR as database type.

Action:
Ensure that the schemas to be consolidated are not created using EBR database type.

RCU-06156
Validation of edition failed.

Category:
Repository Configuration

Cause:
Edition was not specified or was empty value.

Action:
Specify the value of edition for EBR database type.

RCU-06157
Internal error occurred.

Category:
Repository Configuration

Cause:
Execution of sql query, {0} failed.

Action:
Refer to the RCU logs for details.

RCU-06158
Unable to verify components of the schemas to be consolidated.

Category:
Repository Configuration

Cause:
Error in checking whether the component {0} is consolidatable.

Action:
Refer to the RCU logs for details.

RCU-06159
Invalid command line arguments.

Category:
Repository Configuration

Cause:
Validation of the command line parameters for listSchemas operation failed.

Action:
Refer to the RCU logs for details.

RCU-06160
Invalid database type for "listSchemas" operation.

Category:
Repository Configuration

Cause:
"listSchemas" operation is supported only on ORACLE and EBR

Action:
Provide valid database type.

RCU-06161
Consolidated schema cannot be dropped.

Category:
Repository Configuration

Cause:
Validation of drop consolidated schema failed. Specified consolidated schema was invalid.

Action:
Check the logs for details.

RCU-06162
Invalid consolidated schema name.

Category:
Repository Configuration

Cause:
Consolidated schema name was not provided.

Action:
Provide valid consolidated schema name using "{0}" parameter.

RCU-06163
Invalid schema specified for consolidation.

Category:
Repository Configuration

Cause:
Specified schema {0} was not a valid schema in the schema version registry info.

Action:
Provide valid schema name.

RCU-06164
Invalid schema name specified for drop operation.

Category:
Repository Configuration

Cause:
{0} is not of type "CONSOLIDATED". "-dropConsolidatedSchema" operation can be used only to drop consolidated schemas.

Action:
Specify valid consolidated schema name.

RCU-06165
Invalid consolidated schema name.

Category:
Repository Configuration

Cause:
Consolidated schema name was not provided.

Action:
Provide valid value for {0}.

RCU-06166
Invalid schemas to be consolidated.

Category:
Repository Configuration

Cause:
Consolidated schema list was not provided.

Action:
Provide valid value for {0}.

RCU-06167
Missing command line arguments for consolidate operation.

Category:
Repository Configuration

Cause:
Valid value was not specified for consolidated schema name.

Action:
Provide the argument {0} for consolidate operation.Refer to RCU help for details.

RCU-06168
Missing command line arguments for consolidate operation.

Category:
Repository Configuration

Cause:
Valid value was not specified for schemas to be consolidated.

Action:
Provide the argument {0} for consolidate operation.Refer to RCU help for details.

RCU-06169
Unable to write properties to response file.

Category:
Repository Configuration

Cause:
An IO error occurred while writing into response file.

Action:
Check the log for more details.

RCU-06170
Unable to generate response file.

Category:
Repository Configuration

Cause:
An Internal error happened during response file generation.

Action:
Check the log for more details.

RCU-06171
Initialization of properties from RCU Response template failed.

Category:
Repository Configuration

Cause:
Unable to read the RCUResponse.xml template from RCU jar.

Action:
Contact the administrator to resolve the issue.

RCU-06172
Error in reading properties from RCU Response template.

Category:
Repository Configuration

Cause:
A Jaxb error was thrown while parsing the template xml.

Action:
Check the log for more details.

RCU-06173
Unable to generate RCUResponse file.

Category:
Repository Configuration

Cause:
An error occurred while generating RCUResponse file.

Action:
Check the log for more details.

RCU-06174
Could not create the response file directory

Category:
Repository Configuration

Cause:
Unable to create the response file directory {0}. This could be due to permission related issue.

Action:
Check if neccessary permissions are present to create the directory {0}.

RCU-06175
Could not create response file.

Category:
Repository Configuration

Cause:
Unable to create the response file {0}. This could be due to permission related issue.

Action:
Check if neccessary permissions are present to create the response file {0}.

RCU-06176
{0} is not a valid directory for generating response file.

Category:
Repository Configuration

Cause:
{0} could be a non existent directory or it could already contain an existing response file.

Action:
Choose a different location or clean the directory {0}.

RCU-06177
Unable to use the specified response file location.

Category:
Repository Configuration

Cause:
{0} file already exists under the given directory {1}.

Action:
Specify different directory for response file.

RCU-06178
Unable to use the specified wallet file location.

Category:
Repository Configuration

Cause:
{0} wallet file already exists under the given directory {1}.

Action:
Specify different directory for wallet file.

RCU-06179
An internal error occurred while initializing.

Category:
Repository Configuration

Cause:
Initialization of response file reader failed.

Action:
Check the log for more details and contact the administrator to resolve the issue

RCU-06180
Unsupported RCU Operation

Category:
Repository Configuration

Cause:
No value was specified for the property "operation".

Action:
Refer to the RCU guide or command line help for a list of valid RCU operations.

RCU-06181
Unsupported RCU Operation

Category:
Repository Configuration

Cause:
Value provided for the property "operation" was not a valid RCU operation.

Action:
Refer to the RCU guide or command line help for a list of valid RCU operations.

RCU-06182
No value specified for a mandatory property.

Category:
Repository Configuration

Cause:
Value for property "{0}" was not provided in the response file.

Action:
Provide valid value in the response file.

RCU-06183
Some properties in the response file are missing values.

Category:
Repository Configuration

Cause:
Some of the mandatory properties in the response file were missing values.

Action:
Refer to the log for details.

RCU-06184
An internal error occurred while initializing.

Category:
Repository Configuration

Cause:
Error encountered while reading the response file.

Action:
Check the logs for more details and contact the administrator to resolve the issue.

RCU-06185
Invalid response file.

Category:
Repository Configuration

Cause:
Response file was either null or it did not have read permissions.

Action:
Provide a valid response file.

RCU-06186
Invalid "schemaPrefix" for generating wallet.

Category:
Repository Configuration

Cause:
"schemaPrefix" cannot be empty while generating wallet.

Action:
Provide a valid "schemaPrefix".

RCU-06187
Invalid "dbUser" for generating wallet

Category:
Repository Configuration

Cause:
"dbUser" could not be empty while generating wallet.

Action:
Provide a valid "dbUser".

RCU-06188
Invalid "schemaName" for generating wallet

Category:
Repository Configuration

Cause:
"schemaName" could not be empty while generating wallet.

Action:
Provide a valid "schemaName".

RCU-06189
Unable to create Oracle wallet

Category:
Repository Configuration

Cause:
Directory {0} was either not found or was not a directory.

Action:
Provide a valid directory path.

RCU-06190
Unable to create Oracle Wallet at {0}.

Category:
Repository Configuration

Cause:
An internal error occurred while creating Oracle Wallet at {0}.

Action:
Check the log for more details and contact the administrator to resolve the issue.

RCU-06191
Unable to get wallet data for alias {0} from {1}.

Category:
Repository Configuration

Cause:
A file read error occurred while reading data from wallet {1}

Action:
Make sure that the wallet file has read permissions.

RCU-06192
Specified wallet location is not a valid directory.

Category:
Repository Configuration

Cause:
Wallet location specified did not exist.

Action:
Provide a valid wallet location.

RCU-06193
Wallet alias is not valid.

Category:
Repository Configuration

Cause:
Specified value for wallet alias was empty.

Action:
Provide a valid wallet alias.

RCU-06194
Unable to add entry {0} to wallet at {1}.

Category:
Repository Configuration

Cause:
A file read or write error or a security error was thrown while writing into wallet at {1}.

Action:
Check the log for more details and contact the administrator to resolve the issue.

RCU-06195
Invalid wallet directory location for creating wallet.

Category:
Repository Configuration

Cause:
Specified location {0} had wallet file in it.

Action:
Provide different directory location for creating wallet.

RCU-06196
Unable to create directory {0}.

Category:
Repository Configuration

Cause:
A file read or write error occurred while creating directory {0}.

Action:
Check if you have permissions to create the directory {0}. Contact the administrator if problem persists.

RCU-06197
Invalid arguments specified for the {1} operation.

Category:
Repository Configuration

Cause:
Some of the argument(s) specified, "{0}" were not valid for the {1} operation.

Action:
Refer to the RCU guide or command line help for list of valid arguments.

RCU-06198
invalid SSL arguments.

Category:
Repository Configuration

Cause:
SSL authentication requires client and server authentication or encryption details.

Action:
Provide the properties as key-value pair separated by comma using the argument "-sslArgs".

RCU-06199
invalid "serverDN" value.

Category:
Repository Configuration

Cause:
Value for "serverDN" was not provided. "serverDN" is a mandatory parameter for SSL connection.

Action:
Provide a valid value for "serverDN" argument. To disable the serverDN check, provide the property "oracle.net.ssl_server_dn_match=false" in "-sslArgs".

RCU-06200
Error while validating TDE check on database.

Category:
Repository Configuration

Cause:
TDE was not enabled in the database.

Action:
Specify "-encryptTablespace false" argument.

RCU-06202
RCUCommandLine Error - validation of RCU command line options failed.

Category:
Repository Configuration

Cause:
Invalid command line option was specified.

Action:
Provide one of the following options:

RCU-06203
Invalid script location is provided.

Category:
Repository Configuration

Cause:
Script Location was not provided or was empty string.

Action:
Specify a valid location.

RCU-06204
Specified script location is invalid.

Category:
Repository Configuration

Cause:
The specified directory did not exist.

Action:
Specify an existing directory.

RCU-06205
Database type validation failed.

Category:
Repository Configuration

Cause:
Invalid database type. Valid database types are: {0}

Action:
Provide valid database type.

RCU-06206
invalid Component {0}.

Category:
Repository Configuration

Cause:
Skipping {0} component as config or storage file was missing for the component.

Action:
Specify a valid component name.

RCU-06250
Internal Error while parsing component metadata files.

Category:
Repository Configuration

Cause:
Specified schema base definition {0} not found in the Oracle Home. Schema base definition of {1} was wrong.

Action:
Check the logs for more details and contact the administrator to resolve the issue.

RCU-06251
Drop repository validation failed.

Category:
Repository Configuration

Cause:
Component "{0}" could not be dropped independently.

Action:
Specify schema base component "{0}" to drop component "{1}".

RCU-06252
Consolidated component is not found in the Oracle Home.

Category:
Repository Configuration

Cause:
Component "{0}" is consolidated to the schema of the component "{1}". For dropping consolidated schema, all the consolidated components have to be present in the Oracle Home.

Action:
Invoke dropRepository from Oracle Home which contains the component {0}.

RCU-06253
Tablespace configuration of component "{0}" cannot be overridden.

Category:
Repository Configuration

Cause:
Component "{0}" is consolidated to the schema of the component "{1}". "{0}" could not configure custom tablespace.

Action:
Override the tablespace configuration of the component "{0}" which will be used by the component "{1}" also.

RCU-06254
Drop repository validation failed.

Category:
Repository Configuration

Cause:
Component(s) "{0}" could not be dropped independently.

Action:
Select corresponding schema base component(s) "{0}" to drop component(s) "{1}".

RCU-06255
Drop repository validation failed.

Category:
Repository Configuration

Cause:
Component "{0}" for the prefix "{1}" was created as standalone schema. Component could not be dropped in consolidate mode.

Action:
Disable consolidate mode and drop the component.

RCU-06256
Drop repository validation failed.

Category:
Repository Configuration

Cause:
Component "{0}" for the prefix "{1}" was created as consolidate schema. Component could not be dropped in non-consolidate mode.

Action:
Enable consolidate mode and drop the component.

RCU-06257
Create repository validation failed.

Category:
Repository Configuration

Cause:
Consolidated schema component "{0}" for the prefix "{1}" could not be created. The specified prefix was already in use for some of the standalone schemas.

Action:
Specify different prefix.

RCU-06258
Host name or IP address validation failed.

Category:
Repository Configuration

Cause:
An invalid host name or IP address {0} was specified.

Action:
Enter a valid host name or IP address.

RCU-06259
Component validation failed.

Category:
Repository Configuration

Cause:
Incompatible components {0}, {1} were selected/specified.

Action:
Select/specify either component {0} or component {1}.

RCU-06301
invalid password.

Category:
Repository Configuration

Cause:
Password was not provided for {0} in the wallet.

Action:
Provide a valid password.

RCU-06302
Command line arguments validation failed.

Category:
Repository Configuration

Cause:
Value for "{0}" was not provided.

Action:
Provide values for both "-compInfoXMLLocation" and "-storageXMLLocation" or invoke without any of these arguments.

RCU-06303
internal error

Category:
Repository Configuration

Cause:
Value for "{0}" was not provided in rcu properties file.

Action:
Provide valid values for properties "COMPONENT_INFO_LOCATION" and "STORAGE_INFO_LOCATION" in rcu properties file located at {0}

RCU-07000
The referenced variable validation fails.

Category:
Repository Configuration

Cause:
The referenced variable "{0}" is not defined.

Action:
Provide the required variable value.

RCU-07001
invalid database password.

Category:
Repository Configuration

Cause:
Database password was not provided.

Action:
Specify valid value for database password.

RCU-07002
Validation of SSL arguments fails.

Category:
Repository Configuration

Cause:
SSL arguments are not provided in proper format.

Action:
Refer help for details.

RCU-07003
Command line argument validation fails.

Category:
Repository Configuration

Cause:
Invalid command line argument.

Action:
Refer help for supported arguments. Remove invalid option

RCU-07004
ServerDN validation fails.

Category:
Repository Configuration

Cause:
Value for serverDN is not provided. "serverDN" is mandatory parameter for SSL connection.

Action:
To disable the serverDN check, provide the property "oracle.net.ssl_server_dn_match=false" in "-sslArgs"

RCU-07005
Database connectstring validation fails.

Category:
Repository Configuration

Cause:
Database connectstring is not provided in expected format.

Action:
Refer help for the supported format type.

RCU-07006
Validation of log location failed.

Category:
Repository Configuration

Cause:
Could not create the log directory {0}.

Action:
Make sure that the specified log directory and system temporary directory has write permission.

28

REP-00001 to REP-80012

REP-00001
The Oracle Reports Builder message file cannot be found.

Category:
Other

Cause:
The file of error messages could not be opened or an internal error occurred while opening it.

Action:
Reinstall Oracle Reports Builder or contact Oracle Support Services for assistance.

REP-00002
The string from the message file cannot be retrieved.

Category:
Other

Cause:
Oracle Reports Builder could not retrieve the necessary error message or string.

Action:
For assistance, contact Oracle Support Services.

REP-00003
Global preference file cannot be opened.

Category:
Other

Cause:
The global preference file could not be opened. This is just a warning, so the product will continue to run even if this occurs. The possible causes of this error include the following: Case 1: The file was not found under the specified name in the specified location. Case 2: Lack of necessary privileges to open the file. Case 3: A system error made it impossible to open the file.

Action:
Take the following actions to correct this error: If Case 1: Verify that the file named prefs.ora is stored in the appropriate directory. For more information, contact the database administrator. If Case 2: Verify privileges necessary to access the file, and change privileges accordingly. If Case 3: Consult the operating system documentation or the system administrator.

REP-00004
User preference file cannot be opened.

Category:
Other

Cause:
The local (customized) preference file could not be opened. This is just a warning, so the product will continue to run even if this occurs. The possible causes of this error include the following: Case 1: The file was not found under the specified name in the specified location. Case 2: Lack of necessary privileges to open the file. Case 3: A system error made it impossible to open the file.

Action:
Take the following actions to correct this error: If Case 1: Verify the file prefs.ora is located in the home directory, and change the directory and/or file name as appropriate. If Case 2: Verify privileges necessary to access the file, and change privileges accordingly. If Case 3: Consult the operating system documentation or contact the system administrator.

REP-00005
A syntax error exists at line {0} in global preference file.

Category:
Other

Cause:
One or more of the preferences in the global preference file was specified incorrectly on the line number shown in the message. The most likely cause of this error is that the file has been edited and one or more preferences incorrectly specified. As a result, the Oracle Reports Builder will ignore the incorrectly specified preferences.

Action:
Edit the global preference file and ensure that all preferences are correctly specified, and make the necessary updates.

REP-00006
A syntax error exists at line {0} in user preference file.

Category:
Other

Cause:
One or more of the preferences in the user preference file was specified incorrectly on the line number shown in the message. The most likely cause of this error is that the file has been edited and one or more preferences incorrectly specified. As a result, the Oracle Reports Builder will ignore the incorrectly specified preferences.

Action:
Edit the global preference file and ensure that all preferences are correctly specified. If they are not, make the necessary updates.

REP-00007
The user preference file cannot be written to.

Category:
Other

Cause:
An attempt was made to save preferences and the user preference file could not be written. The possible causes of this error include the following: Case 1: Lack of necessary privileges to write the file. Case 2: A system error made it impossible to write the file.

Action:
Take the following actions to correct this error: If Case 1: Verify privileges necessary to write the file, and change the privileges accordingly. If Case 2: Consult the operating system documentation or contact the system administrator.

REP-00008
An unexpected memory error occurred while initializing preferences.

Category:
Memory

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00058
Data passing to a remote Reports Server is not supported.

Category:
Data

Cause:
A record group was passed to a report to be run remotely.

Action:
Do not specify a Reports Server when passing a record group.

REP-00059
Resources for subcomponent {0} cannot be located.

Category:
Other

Cause:
One of the subcomponents of the Oracle Reports Builder could not locate its resource file. Possible causes of this error include: Case 1: The resource file does not exist. Case 2: The resource file is in the wrong place. Case 3: The environment is not configured properly.

Action:
Take the following actions to correct this error: If Case 1: Verify that the resource files are present. If Case 2: Verify that the resource files are in the proper directory. If Case 3: Verify that the environment is set correctly. On UNIX, verify that the proper environment variable is set; on Windows, check oracle.ini.

REP-00060
A synchronous job cannot be run concurrently with another report.

Category:
Other

Cause:
An attempt was made to run a report initiated by Forms Runtime and requiring data passed from that tool, but one or more other reports are running or queued to run. Reports requiring passed data must be run immediately.

Action:
Wait for all other reports currently listed in the Reports Server queue to run, then rerun report.

REP-00061
An internal error occurred - rxmobfree: reference count is zero.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00062
An internal error occurred - rxmobnew: size mismatch.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00063
An internal error occurred - rxmobnew: memory manager mismatch.

Category:
Memory

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00064
An internal error occurred - rxmobnew: type mismatch.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00065
A virtual memory system error occurred.

Category:
Memory

Cause:
Oracle Reports Builder has encountered a memory error.

Action:
Make note of the error-specific code and contact Oracle Support Services.

REP-00066
An error occurred executing the CA utility.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00067
The value for keyword STYPE is invalid.

Category:
Other

Cause:
In Reports Converter, an invalid value was provided for the STYPE keyword.

Action:
Check the syntax of the keyword. Valid values are DATABASE, REXFILE, RDFFILE, PLLDB, PLLFILE, or PLDFILE. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00068
The value for DTYPE is invalid.

Category:
Other

Cause:
In Reports Converter, an invalid value was provided for the DTYPE keyword.

Action:
Check the syntax of the keyword. Valid value are DATABASE, REXFILE, RDFFILE, REPFILE, TDFFILE, PLLDB, PLLFILE, PLXFILE, or PLDFILE. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00069
An internal error occurred

Category:
Other

Cause:
An Oracle Reports Builder internal code error occurred.

Action:
For assistance, contact Oracle Support Services.

REP-00071
The SSL context cannot be allocated.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00072
The NNIT interface cannot be initialized.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00073
An unknown product cannot be run.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00074
An attempt to run another product using SSL failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00075
An error occurred when running the called Oracle component,

Category:
Other

Cause:
Oracle Reports Builder encountered an error after calling Forms Runtime or Graphics Runtime. The accompanying error message displays the error encountered by the called application.

Action:
Resolve the error encountered by the called application and retry the operation.

REP-00076
An internal failure occurred in product integration.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00077
The column in query {0} too long for data passing.

Category:
Data

Cause:
An attempt was made to pass data to a column of excessive size (likely a LONG column).

Action:
Remove the column from the report definition and the calling document's definition.

REP-00078
A single process integration was invoked with BATCH=NO.

Category:
Process

Cause:
An attempt was made to invoke Oracle Reports Builder specifying BATCH=NO with executable in which Oracle Reports Builder is linked with another product.

Action:
Use an executable which integrates using multiple processes, or specify BATCH=YES.

REP-00079
Value for keyword OVERWRITE is invalid.

Category:
Other

Cause:
In Reports Converter, an invalid value was specified for the OVERWRITE keyword.

Action:
Reenter the command, specifying a value of YES, NO, or PROMPT for the OVERWRITE keyword.

REP-00080
The specified value is invalid.

Category:
Other

Cause:
In Reports Converter, OVERWRITE=PROMPT was specified on the command line, then a value other than YES or NO was entered when prompted.

Action:
Specify a value of YES or NO at the prompt, or CANCEL the operation.

REP-00081
An error occurred during the file I/O operation.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00082
An error occurred executing the SCA utility.

Category:
Other

Cause:
The possible causes of this error include the following: Case 1: The initialization file is not current. Case 2: An abnormal condition.

Action:
Take the following actions to correct this error: If Case 1: Ensure that the directory where the report is located is defined in the REPORTS_PATH located in $ORACLE_HOME/bin/reports.sh. If Case 2: For assistance, contact Oracle Support Services.

REP-00083
The value for keyword DUNIT is invalid.

Category:
Other

Cause:
In Reports Converter, an invalid value was specified for the DUNIT keyword.

Action:
Check the syntax of the keyword. Valid values are CENTIMETER, CHARACTER, INCH, or POINT. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00084
The value for keyword PAGESIZE is invalid.

Category:
Other

Cause:
In Reports Converter, an invalid value was specified for the PAGESIZE keyword.

Action:
Check the syntax and value of the keyword. Valid syntax is <width>x<height>. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00085
The value for keyword FORMSIZE is invalid.

Category:
Other

Cause:
In Reports Converter, an invalid value was specified for the FORMSIZE keyword.

Action:
Check the syntax and value of the keyword. Valid syntax is <width>x<height>. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00086
DUNIT must be different than source report's unit of measurement.

Category:
Other

Cause:
In Reports Converter, an invalid value was specified for the DUNIT keyword that was in the same unit of measurement as the report to be converted.

Action:
Check the syntax and value of the keyword. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00087
The value for keyword DESTYPE is invalid.

Category:
Other

Cause:
In Reports Runtime, an invalid value was specified for the DESTYPE keyword.

Action:
Check the syntax and value of the keyword. Valid values are SCREEN, FILE, PRINTER, MAIL, SYSOUT, or PREVIEW. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00088
The value for keyword ONSUCCESS is invalid.

Category:
Other

Cause:
An invalid value was specified for the ONSUCCESS keyword.

Action:
Specify COMMIT, ROLLBACK, or NOACTION either in the Runtime Settings tab of the Tools Options dialog or on the command line. To check the command line syntax, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00089
The value for keyword ONFAILURE is invalid.

Category:
Other

Cause:
An invalid value was specified for the ONFAILURE keyword.

Action:
Specify COMMIT, ROLLBACK, or NOACTION either in the Runtime Settings tab of the Tools Options dialog or on the command line. To check the command line syntax, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00090
The value for keyword ACCESS is invalid.

Category:
Other

Cause:
For Oracle Reports Builder, an invalid value was specified for the ACCESS keyword.

Action:
Specify FILE or DATABASE. To check the command line syntax, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00091
The value for parameter {0} is invalid.

Category:
Other

Cause:
An invalid value was specified for the named parameter. For example, in the Reports Runtime command string, a character value was provided for a parameter with a data type of Number.

Action:
Retry the operation, specifying a valid value for the parameter.

REP-00092
Version 1.1 LANGUAGE argument not supported. Use Oracle National Language environment variable instead

Category:
Other

Cause:
For Oracle Reports Builder or Runtime, the LANGUAGE keyword was included in the command line string.

Action:
Remove the LANGUAGE argument string from the command string, and set the Oracle National Language environment variable NLS_LANG to the appropriate value.

REP-00094
FORMSIZE must be 80x24 if DUNIT is Character.

Category:
Other

Cause:
While using Reports Converter with DUNIT=Character, a Parameter Form size was specified that was not equal to 80x24.

Action:
The character-mode Parameter Form size must be 80x24. Either specify a FORMSIZE of 80x24 when DUNIT=Character, or do not specify a FORMSIZE.

REP-00095
The value for keyword ORIENTATION is invalid.

Category:
Other

Cause:
An invalid value was specified for the ORIENTATION keyword.

Action:
Specify DEFAULT, LANDSCAPE, or PORTRAIT either in the Runtime Settings tab of the Tools Options dialog box or on the command line. To check the command line syntax, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00096
The value for keyword MODE is invalid.

Category:
Other

Cause:
An invalid value was specified for the MODE keyword.

Action:
Specify DEFAULT, BITMAP, or CHARACTER either in the Runtime Settings tab of the Tools Options dialog or on the command line. To check the command line syntax, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00097
The value for keyword TRACEMODE is invalid.

Category:
Other

Cause:
Either an invalid or no value was specified for the TRACEMODE keyword, or keywords were specified out of order on the command line without being named.

Action:
Either specify Append or Replace for Trace Mode in the Trace Settings dialog or TRACE_APPEND or TRACE_REPLACE on the command line, or check the syntax of the command. To check the command line syntax, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00098
The report was not run as it was canceled in the Parameter Form.

Category:
Other

Cause:
The report was not executed because Cancel instead of Run Report was selected in the Runtime Parameter Form.

Action:
No action is necessary.

REP-00099
The report is aborted upon user request.

Category:
Other

Cause:
The report was stopped while it was executing.

Action:
No action is necessary.

REP-00100
The file pointer in file {0} cannot be positioned.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00101
File {0} cannot be read.

Category:
Other

Cause:
Oracle Reports Builder tried to read a file, which could be opened but not read.

Action:
Consult the operating system documentation or contact the system administrator.

REP-00102
File {0} cannot be written to.

Category:
Other

Cause:
Oracle Reports Builder tried to write the file shown in the message and could not. The possible causes of this error include the following: Case 1: Lack of necessary privileges to write the file. Case 2: The file system does not have enough room for the file. Case 3: A system error made it impossible to open the file.

Action:
Take the following actions to correct this error: If Case 1: Verify the privileges necessary to write the file, and change privileges accordingly. If Case 2: Make more room by deleting unnecessary files or expanding storage. If Case 3: Consult the operating system documentation or contact the system administrator.

REP-00103
File {0} cannot be closed.

Category:
Other

Cause:
Oracle Reports Builder tried to close the file, but was unsuccessful. The most likely reason is that a system error made it impossible to close the file.

Action:
Consult the operating system documentation or contact the system administrator.

REP-00104
File {0} cannot be deleted.

Category:
Other

Cause:
Oracle Reports Builder tried to delete the file shown, but was unsuccessful. The most likely reason is that a system error made it impossible to delete the file.

Action:
Consult the operating system documentation or contact the system administrator.

REP-00105
File {0} cannot be locked in exclusive mode.

Category:
Other

Cause:
Oracle Reports Builder tried to lock the file shown, but was unsuccessful. The most likely reason is that a system error made it impossible to lock the file.

Action:
Consult the operating system documentation or contact the system administrator.

REP-00106
File {0} cannot be locked in shared mode.

Category:
Other

Cause:
Oracle Reports Builder tried to lock the file shown, but was unsuccessful. The most likely reason is that a system error made it impossible to lock the file.

Action:
Consult the operating system documentation or contact the system administrator.

REP-00107
File {0} cannot be opened: bad name.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00108
File {0} cannot be found.

Category:
Other

Cause:
Oracle Reports Builder tried to access the file shown, but could not find it.

Action:
Verify the file name. Specify a directory before the file name, or modify the REPORTS_PATH environment variable to include the directory where the file is located.

REP-00109
There are too many files open.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00110
File {0} cannot be opened.

Category:
Other

Cause:
Oracle Reports Builder tried to open the file shown and could not. The possible causes of this error include the following: Case 1: The file was not found under the specified name in the specified location. Case 2: Lack of necessary privileges to open the file. Case 3: A system error made it impossible to open the file.

Action:
Take the following actions to correct this error: If Case 1: Verify that the file is stored in the specified directory under the specified name. If it is not, change the directory and/or file name as appropriate. If Case 2: Verify the privileges necessary to open the file, and change the privileges accordingly. If Case 3: Consult the operating system documentation or contact the system administrator.

REP-00111
Directory {0} is protected.

Category:
Other

Cause:
Oracle Reports Builder attempted to read from or write to a directory that is read and write protected.

Action:
Change the permissions on the directory as necessary.

REP-00112
File {0} is write-protected.

Category:
Other

Cause:
Oracle Reports Builder attempted to write to a file that is write-protected.

Action:
Change the permissions of the file as necessary.

REP-00113
File {0} is read-protected.

Category:
Other

Cause:
Oracle Reports Builder attempted to read a file that is read-protected.

Action:
Change the permissions of the file as necessary.

REP-00114
File {0} no longer exists.

Category:
Other

Cause:
Oracle Reports Builder attempted to access a file that no longer exists.

Action:
Remove the call to the file, re-create the file, or specify a different file.

REP-00115
Directory {0} cannot be read.

Category:
Other

Cause:
Oracle Reports Builder attempted to read from or write to a directory that does not exist.

Action:
Verify that the specified directory exists.

REP-00116
Directory {0} cannot be accessed.

Category:
Other

Cause:
Oracle Reports Builder could not access the specified directory.

Action:
Consult the system administrator.

REP-00117
Exit to the host operating system failed.

Category:
Operating System

Cause:
Oracle Reports Builder attempted to exit the program and return control to the host operating system.

Action:
No action is necessary.

REP-00118
A temporary file cannot be created.

Category:
Other

Cause:
Oracle Reports Builder tried to create a temporary file but could not do so. The possible causes of this error include the following: Case 1: The environment variable that determines in what directory to create temporary files is set to an invalid directory. Case 2: There is not enough free space on the disk to create the temporary file. Case 3: A temporary file that cannot be modified already exists.

Action:
Take the following actions to correct this error: If Case 1: Set the environment variable for temporary files to a valid directory. If Case 2: Free up some space on the disk. If Case 3: Remove the existing temporary file, if possible.

REP-00119
File link boilerplate {0}'s Source Filename {1} cannot be found.

Category:
Other

Cause:
Oracle Reports Builder could not find the source file specified in the Source Filename property for the file link boilerplate object. The possible causes of this error include the following: Case 1: The file was not found under the specified name in the specified location. Case 2: Lack of necessary privileges to open the file. Case 3: A system error made it impossible to open the file.

Action:
Take the following actions to correct this error: If Case 1: Verify that the file is stored in the specified directory under the specified name. If it is not, change the directory and/or file name as appropriate. If Case 2: Verify the privileges necessary to open the file, and change the privileges accordingly. If Case 3: Consult the operating system documentation or contact the system administrator.

REP-00120
Graph {0}'s associated document {1} cannot be found.

Category:
Other

Cause:
Oracle Reports Builder was unable to find the graph document. The possible causes of this error include the following: Case 1: The graph document was not found under the specified name in the specified location. Case 2: Lack of necessary privileges to open the graph document. Case 3: A system error made it impossible to open the graph document.

Action:
Take the following actions to correct this error: If Case 1: Verify that the graph document is stored in the specified directory under the specified name. If it is not, change the directory and/or file name as appropriate. If Case 2: Verify the privileges necessary to open the graph document, and change the privileges accordingly. If Case 3: Consult the operating system documentation or contact the system administrator.

REP-00124
The temporary file cannot be written to.

Category:
Other

Cause:
Oracle Reports Builder tried to write to the temporary file but could not do so.

Action:
Free up some space on the disk.

REP-00125
An internal error occurred: Unable to load NLS character set.

Category:
Other

Cause:
ORA_NLS was not set, or the directory to which it points does not exist.

Action:
Set ORA_NLS to point to the NLS directory containing character set files.

REP-00126
File {0} is not a known type to Oracle Reports Builder. No file conversion can be performed. Check in anyway?

Category:
Other

Cause:
An attempt was made to check in a file of a type that Oracle Reports Builder cannot convert. For example, Oracle Reports Builder cannot convert a Form Builder (FMB) file.

Action:
To continue checking in, click Yes. Otherwise, click No and nothing will be checked in.

REP-00127
File {0} is not a known type to Oracle Reports Builder. No file conversion can be performed. Check out anyway?

Category:
Other

Cause:
An attempt was made to check out a file of a type that Oracle Reports Builder cannot convert. For example, Oracle Reports Builder cannot convert a Form Builder (FMB) file.

Action:
To continue checking out, click Yes. Otherwise, click No and nothing will be checked out.

REP-00128
There are unsaved changes in file {0}. Save before checkin?

Category:
Other

Cause:
An attempt was made to check in a file that is currently open and there are unsaved changes.

Action:
To save and check in the file, click Yes. Click No to check in the file without the changes. Otherwise, click Cancel and nothing will be checked in.

REP-00129
There are unsaved changes in file {0}. Check out anyway?

Category:
Other

Cause:
An attempt was made to check out a file that is is currently open and there are unsaved changes.

Action:
To check out the file, click Yes. Note that this will overwrite all the changes made to this file. Otherwise, click No and nothing will be checked out.

REP-00130
A module saved in the database cannot be checked in. Save it to file before checkin.

Category:
Other

Cause:
Checking in a module saved in the database is not supported.

Action:
Save the module to the filesystem first and then check it in again.

REP-00131
The communication layer cannot be initialized.

Category:
Other

Cause:
The required communication files were not found.

Action:
Check the installation and setup and update with the latest patch.

REP-00132
A JVM cannot be started.

Category:
Other

Cause:
Oracle Reports could not start up the required JVM services.

Action:
Check the installation and setup and update with the latest patch.

REP-00133
Java Classes cannot be found.

Category:
Other

Cause:
Some required files were not found. This could be caused by an invalid installation or missing files.

Action:
Check the installation and setup and update with the latest patch.

REP-00150
There are too many arguments.

Category:
Other

Cause:
More than the allowable number of arguments for the command were entered.

Action:
Check the syntax of the command. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual. Reenter the command correctly.

REP-00151
Duplicate arguments are specified for keyword {0}.

Category:
Other

Cause:
An argument was entered more than once for the keyword shown. The possible causes of this error include the following: Case 1: A positional argument was entered for the keyword and then the keyword was entered with another argument. Case 2: The same keyword was entered twice (for example, KEYWORD1=YES and KEYWORD1=NO).

Action:
Check the syntax of the command (see the Command Line Keywords appendix in the Publishing Reports to the Web manual). Take the following actions to correct this error: If Case 1: Reenter the command with just the positional argument or just the keyword argument. If Case 2: Reenter the command specifying the keyword only once.

REP-00152
A positional argument is specified after a keyword.

Category:
Other

Cause:
On the command line, an argument was entered without its keyword after being an argument was entered with its keyword. Once a keyword is used on the command line, all subsequent arguments must use keywords as well.

Action:
Reenter the command making sure that no positional arguments (arguments where the keyword is implicit) are specified after arguments with keywords.

REP-00153
Multiple values are not allowed for keyword {0}.

Category:
Other

Cause:
In the command, more than the allowable number of values for the keyword were entered. For example, KEYWORD=(A, B) was entered, where KEYWORD accepts only a single value.

Action:
Check the syntax of the command. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual. Reenter the command without the extra values.

REP-00154
The command file cannot be opened.

Category:
Other

Cause:
A command referenced the command file shown and the file could not be opened. The possible causes of this error include the following: Case 1: The file was not found under the

specified name in the specified location. Case 2: Lack of necessary privileges to open the file. Case 3: A system error made it impossible to open the file.

Action:
Take the following actions to correct this error: If Case 1: Verify that the file is stored in the specified directory under the specified name. If it is not, change the directory and/or file name or move the file into the specified directory. If Case 2: Verify the privileges necessary to access the file, and change the privileges accordingly. If Case 3: Consult the operating system documentation or contact the system administrator.

REP-00155
The value for keyword {0} is invalid.

Category:
Other

Cause:
The value entered for the keyword shown was not a valid value.

Action:
Check the syntax of the keyword. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual. Reenter the command with the appropriate value for the keywords.

REP-00156
The value for keyword DESTYPE is invalid.

Category:
Other

Cause:
In Reports Runtime, an invalid value was provided for the DESTYPE keyword.

Action:
Check the syntax of the keyword. Valid values are SCREEN, FILE, PRINTER, MAIL or SYSOUT. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual. Reenter the command with the appropriate value for the keywords.

REP-00157
The value for {0} must be either YES or NO.

Category:
Other

Cause:
A value other than YES or NO was entered for the keyword shown, and the keyword only accepts YES or NO.

Action:
Reenter the command using a value of YES or NO for the keyword shown.

REP-00158
The command line keyword {0} is unknown.

Category:
Other

Cause:
The referenced string was entered as a keyword, but there is no such keyword.

Action:
Check the syntax of the command. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual. Reenter the command with the appropriate value for the keywords.

REP-00159
A syntax error exists on the command line.

Category:
Other

Cause:
The string entered on the command line could not be parsed. The most likely cause of this error is that quotation marks or parentheses were entered without matching end quotation marks or parentheses.

Action:
Check the syntax of the command. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual. Reenter the command using the appropriate syntax.

REP-00160
A syntax error exists in the command file.

Category:
Other

Cause:
Something entered in the command file could not be parsed. The most likely cause of this error is that quotation marks or parentheses were entered without matching end quotation marks or parentheses.

Action:
Check the syntax of the commands. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual. Edit the file and modify the commands as necessary to correct the commands.

REP-00161
No command-line arguments are specified.

Category:
Other

Cause:
Reports Converter was invoked without specifying any command-line arguments.

Action:
Specify the appropriate command-line arguments (for example, SOURCE, DEST) for Reports Converter. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00162
The value for keyword SHOWWINDOW is invalid.

Category:
Other

Cause:
The value specified for the SHOWWINDOW keyword was not valid.

Action:
Check the syntax of the keyword. Valid values are DEFAULT, WIZARD, and PREVIEWER. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00163
The value for keyword DESTYPE is invalid.

Category:
Other

Cause:
The value specified for the DESTYPE keyword was not valid for the Reports Server.

Action:
Check the syntax of the keyword. Valid values are FILE, PRINTER, MAIL, or CACHE.

REP-00164
The value for keyword PARAMFORM is invalid.

Category:
Other

Cause:
The value specified for the PARAMFORM keyword was not valid.

Action:
Reenter the command, specifying a value of YES, NO, or HTML[action] for the PARAMFORM keyword.

REP-00165
The value for keyword SITENAME is missing.

Category:
Other

Cause:
No value was specified for the SITENAME keyword. A value is required for SITENAME in order to schedule a report.

Action:
Specify a WEBDB site name for the keyword SITENAME.

REP-00166
Read/write of the specified directory is not allowed.

Category:
Other

Cause:
Oracle Reports attempted to read from or write to a directory without read/write privileges.

Action:
Check the command line options to identify the directory name. Add the directory to REPORTS_PATH, ORACLE_PATH, or the sourceDir property in the engine element in the server configuration file.

REP-00171
Output from the remote server cannot be retrieved.

Category:
Other

Cause:
An error occurred when retrieving output from the remote server.

Action:
Verify that the file is accessible, and that the server is set to allow retrieving outputs.

REP-00172
The value for keyword SERVER is missing.

Category:
Other

Cause:
No value was specified for the mandatory keyword SERVER.

Action:
Provide a valid argument for the keyword SERVER and rerun the command.

REP-00173
The value for keyword SHOWJOBS is invalid.

Category:
Other

Cause:
In the Reports Queue Viewer, an argument provided in command line for the SHOWJOBS keyword was not valid.

Action:
Reenter the command, specifying a value of PAST, CURRENT or FUTURE for the SHOWJOBS keyword.

REP-00174
An internal error occurred while obtaining the Reports Server queue information.

Category:
Other

Cause:
The Reports Server did not return valid information about its queue to the queue viewer. This could be caused by one of the following reasons: Case 1: The connection to the Reports Server unexpectedly went down. Case 2: The Reports Server is in an unstable state, or has been shut down.

Action:
Verify that the Reports Server is running. Contact the system administrator and retry the command after verifying that the Reports Server is running. If this problem persists, contact Oracle Support Services.

REP-00175
An internal error occurred while obtaining the Reports Server properties information.

Category:
Other

Cause:
The Reports Server did not return valid information about its properties to the queue viewer. This could be caused by one of the following reasons: Case 1: The connection to the Reports Server unexpectedly went down. Case 2: The Reports Server is in an unstable state, or has been shut down.

Action:
Verify that the Reports Server is running. Contact the system administrator and retry the command after verifying that the Reports Server is running. If this problem persists, contact Oracle Support Services.

REP-00176
Server {0} is shutting down.

Category:
Other

Cause:
A report cannot be submitted when the specified Reports Server is shutting down.

Action:
Submit to another Reports Server or wait until the Server is back up.

REP-00177
An error occurred while running in a remote server.

Category:
Other

Cause:
An attempt to run a command line in the remote server failed.

Action:
Check the command line.

REP-00178
Reports Server {0} cannot establish connection.

Category:
Other

Cause:
A proper connection could not be established to the specified Reports Server.

Action:
Check the network and check the status of the Reports Server in question.

REP-00179
Report execution terminated unexpectedly while running.

Category:
Other

Cause:
The Reports Engine has crashed while running.

Action:
Contact the system administrator.

REP-00180
The report has been canceled from the Reports Server.

Category:
Other

Cause:
The report was stopped while it was executing or removed from the queue before it was started.

Action:
No action is necessary.

REP-00181
An error occurred reading or writing the configuration file for the Reports Server.

Category:
Configuration

Cause:
The configuration file cannot be opened, or its content is incomprehensible.

Action:
Check the configuration file and its access rights. Restart the server.

REP-00182
A syntax error occurred on command line for the Reports Server.

Category:
Other

Cause:
The string entered on the command line could not be parsed. The most likely cause of this error is that quotation marks or parentheses were entered without matching end quotation marks or parentheses.

Action:
Check the syntax of the command. For more information, see the Command Line Keywords appendix in the Publishing Reports to the Web manual. Reenter the command using the appropriate syntax.

REP-00183
TNSNAME must be provided to start up the Reports Server.

Category:
Other

Cause:
An attempt was made to start up the Reports Server without specifying the TNSNAME to which the Server should listen.

Action:
Specify the TNSNAME as a command-line argument.

REP-00184
The specified MAXCONNECTS is out of range.

Category:
Other

Cause:
The MAXCONNECTS value specified is out of range for this platform. MAXCONNECTS must be at least 2, and cannot exceed 4096, and on some platforms the limit is even lower.

Action:
Specify an appropriate value.

REP-00185
Bad load arguments were supplied when starting up the Reports Server.

Category:
Other

Cause:
Inconsistent values were specified among MAXCONNECTS, MINLOAD, MAXLOAD, and INITLOAD.

Action:
Verify that 0 <= MINLOAD <= INITLOAD <= MAXLOAD < MAXCONNECTS.

REP-00186
A daemon cannot listen to the port.

Category:
Other

Cause:
Another daemon may be running that is already listening to the port.

Action:
No action is necessary. Since a daemon is already running, submit the report to be run.

REP-00187
A daemon cannot start up the engine.

Category:
Other

Cause:
A daemon cannot start up the engine executable and communicate with it. This is most likely an installation issue.

Action:
Verify that the installation is done properly.

REP-00188
Reports Server only accepts batch jobs.

Category:
Other

Cause:
A job was submitted to the Reports Server where BATCH=NO, DESTYPE=SCREEN, DESTYPE=PREVIEW, or DESTYPE=SYSOUT.

Action:
These settings are not allowed. Change the command line accordingly.

REP-00189
The Reports Server cache cannot be written to.

Category:
Other

Cause:
Reports Server failed to write to the cache directory.

Action:
Verify that the cache directory is specified in the server configuration file and it is writable.

REP-00190
A report cannot be run to screen in the background.

Category:
Other

Cause:
The report was specified to be run in the background, with DESTYPE=SCREEN. A report cannot run in the background while having its output sent to the screen.

Action:
To send the output to the screen, run it in the foreground. To run the report in the background, specify a different DESTYPE.

REP-00194
A character report cannot be run in bitmap mode using this executable.

Category:
Other

Cause:
Oracle Reports attempted to use the character-mode executable to run a character-mode report with MODE=BITMAP. This is not allowed.

Action:
Change the value of the MODE keyword to match the mode of the executable.

REP-00195
A report cannot be run in bitmap mode to screen using this executable.

Category:
Other

Cause:
Oracle Reports attempted to use the character-mode executable to run a bitmapped report to the screen. This is not allowed.

Action:
Run the report using BATCH=YES or use a bitmapped executable.

REP-00196
The report cannot be run in the background.

Category:
Other

Cause:
BACKGROUND=YES was specified under one of the following conditions, none of which are allowed: Case 1: Running the report from the designer. Case 2: BATCH=YES. Case 3: Running the report using the packaged procedure srw.run_report. Case 4: The platform on running the report does not support spawning of another process.

Action:
Ensure that BACKGROUND=NO when any of the above condition are true.

REP-00197
BATCH=YES or BACKGROUND=YES must be specified on the command line when running a bitmapped report.

Category:
Other

Cause:
Oracle Reports attempted to run a bitmapped report using the character-mode executable in the foreground or during an interactive session. This is not supported.

Action:
To run a bitmapped report using the character-mode executable, specify either BATCH=YES or BACKGROUND=YES (unlike BATCH=YES, this setting provides access to the Runtime Parameter Form).

REP-00200
Enough memory cannot be allocated.

Category:
Memory

Cause:
Oracle Reports Builder cannot obtain enough memory from the system to complete the current task.

Action:
Make more memory available, if possible, or ask the system administrator for assistance.

REP-00201
A zero or negative block size was requested.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00202
A null pointer cannot be freed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00203
A null pointer was passed as a handle.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00204
The handle does not point into an mp block.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00205
There are too many simultaneous locks on one object.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00206
A null cache pointer is passed to virtual memory routine.

Category:
Memory

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00207
The requested block is larger than virtual memory space.

Category:
Memory

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00208
rmaloc was not given a function identifier.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00209
rmaloc was not given a structure identifier.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00210
An illegal operation was requested on a locked handle.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00211
A handle cannot be used after freeing it.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00212
No literal is specified.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00213
An attempt to lock a handle failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00214
A virtual memory buffer of size {0} KB cannot be allocated. Try a smaller size.

Category:
Memory

Cause:
Oracle Reports Builder tried to allocate a virtual memory buffer size at or below the number specified for the BUFFERS keyword.

Action:
Specify a smaller size for BUFFERS, either on the command line or in the Runtime Settings tab of the Preferences dialog box (select Edit, then Preferences), or free up more memory. For command line syntax, see the Command Line Keywords appendix in the Publishing Reports to the Web manual.

REP-00215
An error occurred locking, dereferencing, or freeing a memory handle.

Category:
Memory

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00216
There is insufficient memory to save the report as a JSP or XML.

Category:
Memory

Cause:
The report definition file has exceeded 10 MB. The report cannot be saved as a JSP or XML if it exceeds 10 MB.

Action:
Reduce the size of the file.

REP-00230
An error occurred while starting a thread.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00231
An error occurred while posting thread message.

Category:
Threads

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00232
An error occurred while getting thread message.

Category:
Threads

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00235
The Security Server TNSNAME is not provided in the config file.

Category:
Security

Cause:
Security Server TNSNAME must be specified in config file on security mode"

Action:
Specify Security Server TNSNAME in the config file by using the keyword 'securitytnsname'.

REP-00236
The Security Server cannot be connected.

Category:
Security

Cause:
An abnormal condition was encountered.

Action:
Contact the system administrator. For assistance, contact Oracle Support Services.

REP-00238
Authentication failed.

Category:
Security

Cause:
The system userid/password is invalid or does not have privilege to run the report.

Action:
Check the system userid/password to verify that it is correct or contact the system administrator to grant the necessary privilege.

REP-00239
The Security server authentication failed: invalid user name.

Category:
Security

Cause:
The system user ID is incorrect.

Action:
Check the system user ID to verify that it is correct or contact the system administrator about the system user ID.

REP-00240
The Security Server authentication failed: invalid password.

Category:
Security

Cause:
The password for the system user ID is incorrect.

Action:
Check the system user ID password to verify that it is correct or contact the system administrator about the system user ID password.

REP-00241
The Security Server authentication failed: no privilege on the Reports Server.

Category:
Security

Cause:
The system user ID does not have privilege to access the Reports Server.

Action:
Contact the system administrator about the system user ID's privilege on the Reports Server.

REP-00242
The Security Server authentication failed: no privilege on the printer.

Category:
Security

Cause:
The system user ID does not have privilege to access the printer.

Action:
Contact the system administrator about the system user ID's privilege on the printer.

REP-00243
The Security Server authentication failed: no privilege on the module.

Category:
Security

Cause:
The system user ID does not have privilege to access the module.

Action:
Contact the system administrator about the system user ID's privilege on the module.

REP-00244
The Security Server authentication failed: no privilege of this access type.

Category:
Security

Cause:
The system user ID does not have privilege of this access type.

Action:
Contact the system administrator about the system user ID's privilege of this access type.

REP-00245
The Security Server authentication failed: no privilege of this output type.

Category:
Security

Cause:
The system user ID does not have privilege of this output type.

Action:
Contact the system administrator about the system user ID's privilege of this output type.

REP-00246
The Security Server authentication failed: no privilege for the given time.

Category:
Security

Cause:
The system user ID does not have privilege for the given time.

Action:
Contact the system administrator about the system user ID's privilege for the given time.

REP-00247
The Security Server authentication failed: no privilege for the given date.

Category:
Security

Cause:
The system user ID does not have privilege for the given date.

Action:
Contact the system administrator about the system user ID's privilege for the given date.

REP-00250
A symbol table overflow occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00251
The identifier does not match a defined symbol.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00252
The path specified by environment variable {0} is too long and will be ignored.

Category:
Other

Cause:
The path specified by the environment variable is too long.

Action:
Shorten the length of the designated path.

REP-00253
The total length of the search paths is too long and will be truncated.

Category:
Other

Cause:
The combined length of search paths in the path environment is too long. The combined length cannot exceed 255 characters.

Action:
Shorten the length of one or more paths in the path environment.

REP-00300
An Oracle error occurred.

Category:
Other

Cause:
Oracle Reports Builder encountered an Oracle error.

Action:
Scroll through the error message to see where the error occurred and, if possible, fix it. Otherwise, contact the system administrator.

REP-00301
The SELECT statement may not contain an INTO clause.

Category:
Other

Cause:
An INTO clause was entered in a SELECT statement, which is not allowed in Oracle Reports Builder.

Action:
Remove the INTO clause.

REP-00302
Parameter {0} cannot be found in the report.

Category:
Other

Cause:
Oracle Reports referenced a parameter that is not defined in the report. The most likely cause is that a parameter was deleted but not all references to it were deleted.

Action:
Delete all references to the deleted parameter.

REP-00303
The statement entered is not a SELECT statement.

Category:
Other

Cause:
What was entered in the SELECT Statement field is something other than a SELECT statement. The possible causes of this error include the following: Case 1: Something besides a SELECT statement was entered in the SELECT Statement field. Case 2: An external query was referecned that did not contain a SELECT statement.

Action:
Take the following actions to correct this error: If Case 1: Enter a valid SELECT statement. If Case 2: Modify the external query or reference another external query.

REP-00304
& in SELECT statement was not followed by a valid lexical parameter.

Category:
Other

Cause:
An ampersand (&) appears in the SELECT statement by itself. The possible causes of this error include the following: Case 1: A lexical reference either left out the name of the column or parameter altogether or there is a space between the ampersand and the name of the column or parameter. Case 2: An ampersand was accidentally typed in the SELECT statement.

Action:
Take the following actions to correct this error: If Case 1: Verify that the column or parameter name immediately follows the ampersand with no spaces in between. If Case 2: Delete the ampersand.

REP-00305
Reference {0} cannot be used as a lexical parameter because it is not a character value.

Category:
Other

Cause:
An invalid lexical reference appears in the SELECT statement. Lexical references can only be made to parameters or columns containing character data. The possible causes of this error include the following: Case 1: The wrong column or parameter was referenced. Case 2: The reference should be a bind reference, not a lexical reference. Case 3: The parameter or column referenced was created with a non-character data type.

Action:
Take the following actions to correct this error: If Case 1: Change the name that follows the ampersand (&) so it references a parameter or column with a data type of Character. If Case 2: Replace the ampersand (&) with a colon (:) when referencing the parameter or column. If Case 3: Change the data type of the parameter or column to be Character, if appropriate.

REP-00306
The name {0} is not a valid parameter name.

Category:
Other

Cause:
In making reference to a parameter, an attempt was made to create a parameter with an invalid name. For a bind reference, a parameter definition is automatically created using the name specified in the bind parameter. In this case, Oracle Reports Builder could not create the parameter because the name supplied was not a valid name.

Action:
Check the naming conventions for data model objects and rules for parameter names. Rename the parameter and change the name in the bind reference.

REP-00307
The SELECT statement may not contain a FOR UPDATE clause.

Category:
Other

Cause:
A FOR UPDATE clause was entered in the SELECT statement, which is not allowed in Oracle Reports Builder.

Action:
Remove the FOR UPDATE clause.

REP-00308
An internal error occurred: Unknown column type.

Category:
Other

Cause:
The possible causes of this error include the following: Case 1: An attempt was made to display the value of a column using SRW.MESSAGE, but the column's data type (for example, LONG, LONG RAW, ROWID) is not supported for that operation. Case 2: An attempt was made to pass the value of a column to Forms Runtime or Graphics Runtime as a parameter, but the column's data type (for example, LONG, LONG RAW, ROWID) is not supported for that operation.

Action:
Do not attempt to display or pass this column's value.

REP-00309
The specified database cannot connect after three attempts. Access denied.

Category:
Other

Cause:
Case 1: Some part of the logon string entered was incorrect. After three failed attempts, Oracle Reports Builder displays a dialog box with this message. Case 2: The NLS_LANG environment variable value may be invalid.

Action:
Case 1: Accept the dialog box. Confirm the logon information with the system administrator, if necessary. Go back into Oracle Reports Builder and try connecting to Oracle again. If the problem persists, the system administrator may need to create a new Oracle logon. Case 2: Verify the NLS_LANG value is valid.

REP-00310
An error occurred while processing bind variables in a query.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00311
An internal error occurred: Segmented memory used for lexical parameter.

Category:
Memory

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00312
An internal error occurred: Error dealing with segmented memory.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00313
An internal error occurred: Fetching data records would cause memory overflow.

Category:
Data

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00314
The column name exceeds 256 characters, and no alias is assigned.

Category:
Other

Cause:
One of the SQL SELECT statements contains an expression that is longer than 256 characters, but has no alias.

Action:
Edit the SELECT statement and assign an alias to the expression.

REP-00315
Each SELECT statement must have the same number of columns in a compound query.

Category:
Other

Cause:
A query with a UNION, INTERSECT, or MINUS set operator was entered in which the SELECT statements in the query do not have the same number of selected columns.

Action:
Modify the SELECT statements so that they have the same number of columns.

REP-00316
The types of corresponding columns must match in a compound query.

Category:
Other

Cause:
A query with a UNION, INTERSECT, or MINUS set operator was entered in which corresponding columns have different types. For example, column 1 in the first SELECT statement has data type CHAR, while column 1 in the second SELECT statement has data type NUMBER.

Action:
Modify the SELECT statements so that all corresponding columns have the same data type.

REP-00320
The database cannot be connected.

Category:
Other

Cause:
An attempt to connect to the database failed.

Action:
Recheck the user ID and password and try again.

REP-00321
An internal error occurred: Describe of query failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00322
An internal error occurred: Attempt to put back fetched rows failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00330
An internal error occurred: Location GET_REF parameters failed.

Category:
Other

Cause:
A CDE_MM.GET_REF call in a query did not specify a parameter list.

Action:
Add the parameter list to the call in the query's SELECT statement.

REP-00331
The GET_REF PL/SQL function requires 3 parameters.

Category:
Other

Cause:
The parameter list of a CDE_MM.GET_REF call in a query was incomplete.

Action:
Add the necessary parameters to the call in the query's SELECT statement.

REP-00332
The GET_REF PL/SQL function's last parameter must be of type ROWID.

Category:
Other

Cause:
A parameter of type ROWID was not provided as the last parameter for a GET_REF function.

Action:
Check the parameter list and ensure the last parameter is of type ROWID.

REP-00340
The role password cannot be verified, and the report is not opened.

Category:
Other

Cause:
Incorrect role password. For security reasons, the report cannot be openend.

Action:
Try opening the report again and type in the correct role password.

REP-00341
The roles specified in the report cannot be set, and the report is not opened.

Category:
Other

Cause:
The roles specified in the report cannot be set while opening the report. For security reasons, the report cannot be opened.

Action:
Check role permissions and password.

REP-00342
Roles specified on the command line cannot be set.

Category:
Other

Cause:
The roles specified on the command line cannot be set.

Action:
Check role permissions and password.

REP-00343
Default roles of the current user cannot be set.

Category:
Other

Cause:
Reports is unable to set the default roles of the current user that has passwords.

Action:
Do not use default roles with passwords.

REP-00344
The role password was not confirmed correctly.

Category:
Other

Cause:
The Confirm Password entered is different from the Role Password.

Action:
Reenter and verify that Confirm Password exactly matches the Role Password.

REP-00345
An empty role and a non-empty password is not valid.

Category:
Other

Cause:
No role is specified, while role password is specified.

Action:
Leave all fields empty to not associate a role with this report.

REP-00346
The role must be no longer than {0} characters. It will be truncated.

Category:
Other

Cause:
The role name specified is longer than is allowable. It will be truncated.

Action:
Specify a shorter role name.

REP-00347
The role password must be no longer than {0} characters. It will be truncated.

Category:
Other

Cause:
The role password specified is longer than is allowable. It will be truncated.

Action:
Specify a shorter role password.

REP-00348
The role password is incorrect.

Category:
Other

Cause:
The role password entered was incorrect.

Action:
Reenter with the correct role password.

REP-00450
PL/SQL error {0} was encountered.

Category:
Other

Cause:
Oracle Reports Builder encountered the identified PL/SQL error while running a report.

Action:
Edit and recompile the PL/SQL in the report to avoid this error.

REP-00451
PL/SQL error {0} was encountered. {1}.

Category:
Other

Cause:
Oracle Reports Builder encountered the identified PL/SQL error while running a report.

Action:
Edit and recompile the PL/SQL in the report to avoid this error.

REP-00452
PL/SQL error {0} was encountered. {1}. {2}.

Category:
Other

Cause:
Oracle Reports Builder encountered the identified PL/SQL error while running a report.

Action:
Edit and recompile the PL/SQL in the report to avoid this error.

REP-00453
PL/SQL error {0} was encountered. {1}. {2}. {3}.

Category:
Other

Cause:
Oracle Reports Builder encountered the identified PL/SQL error while running a report.

Action:
Edit and recompile the PL/SQL in the report to avoid this error.

REP-00490
An internal error occurred: Toolkit context unavailable.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00491
Data truncation is possible in column {0}.

Category:
Data

Cause:
The database column's width in the report is defined to be less than its width in the database. This can sometimes occur when the columns in the database are updated subsequent to the report being defined. This warning is raised only when RUNDEBUG is YES.

Action:
Force the query to be reparsed. One method is to type a space at the end of a line in the SELECT Statement field and then accept the SQL Query Statement dialog.

REP-00492
The token {0} is unrecognized.

Category:
Other

Cause:
The SELECT statement entered contains an item that is not part of SQL syntax.

Action:
Review the SELECT statement and ensure that it follows SQL syntax.

REP-00493
An internal error occurred: Unable to expand lexical references.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00494
An internal error occurred: Unable to process lexical references.

Category:
Process

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00495
An internal error occurred: Unable to tokenize the query.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00496
An internal error occurred: Unable to parse the query.

Category:
Other

Cause:
The SQL statement entered cannot be parsed because it contains an error.

Action:
Review the SQL statement to ensure correct syntax. For more information, see the SQL Language Reference Manual.

REP-00497
An internal error occurred: Query failed in rodslt.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00498
The number of columns selected by the query is incompatible with the report definition.

Category:
Other

Cause:
The query is selecting more columns than the report definition is expecting. This can happen when using an external query and the query has been changed since the report was defined.

Action:
Update the report definition so that it accepts the changed query. For example, go to the SQL Query Statement dialog for the query that references the changed external query and modify it. Formulas, summaries, and fields that rely on any changed columns may also need to be updated.

REP-00499
Column {0} selected by the query is incompatible with the report definition.

Category:
Other

Cause:
The column from the database does not match the column in the report definition. The possible causes of this error include the following: Case 1: The definition of the column in the database has changed since the report was defined. Case 2: The report uses an external query and the external query was changed since the report was defined.

Action:
Take the following actions to correct this error: If Case 1: Update the report definition so that it accepts the changed column. For example, if the data type of the column has changed, reaccept the SQL Query Statement dialog external query so the column in the report definition has its data type updated. Formulas, summaries, and fields that rely on the changed column may also need to be updated. If Case 2: Update the report definition so that it accepts the changed query. For example, reaccept the SQL Query Statement dialog that references the changed external query and accept it. Formulas, summaries, and fields that rely on any changed columns may also need to be updated.

REP-00500
The number entered is out of range.

Category:
Other

Cause:
The number specified is too large.

Action:
Check the limits of the field. Look in the chapter where the field is described and enter a number that is within the limits.

REP-00501
The specified database cannot be connected.

Category:
Other

Cause:
Oracle Reports Builder could not connect to Oracle The possible causes of this error include the following: Case 1: The Oracle database is temporarily unavailable. Case 2: The connect information was not valid.

Action:
Take the following actions to correct this error: If Case 1: Retry the operation. Contact the system administrator if the problem persists. Note that after three failed attempts, Oracle Reports Builder closes. If Case 2: Verify the connect information, and try to connect again. Note that after three failed attempts, Oracle Reports Builder closes.

REP-00502
An error occurred attempting to open terminal file {0}.

Category:
Other

Cause:
Oracle Reports Builder was unable to open the terminal definition file specified. Either the name of the file was specified incorrectly after the TERM keyword, or the file was not found.

Action:
Verify the name of the terminal definition file, and its path. If the problem persists, contact the system administrator.

REP-00503
The report name is invalid.

Category:
Other

Cause:
An invalid name was specified for the name of a report.

Action:
Specify a valid report name.

REP-00504
The specified database is not connected.

Category:
Other

Cause:
An attempt was made to perform an operation that requires a connection to the database, but no database connection was established.

Action:
Select File, then Connect to connect to the database.

REP-00505
The width for this column is not valid.

Category:
Other

Cause:
The value entered in Width was invalid. The possible causes of this error include the following: Case 1: Zero or a negative number was entered. Width must be greater than zero. Case 2: Something that was not a number was entered. Case 3: For a column of non-numeric data type, a width of the form (x, y) was entered, where x is the precision and y is the scale. This type of Width specification is only valid when the data type is Number.

Action:
Take the following actions to correct this error: If Case 1: Enter a number greater than zero. If Case 2: Enter a number greater than zero. If Case 3: Enter a number greater than zero or, if possible, change the data type of the column to Number.

REP-00506
Database columns cannot be moved between queries.

Category:
Other

Cause:
An attempt was made to move a column into another group belonging to another query and the column is a database column. A database column must be selected by the query that owns its group.

Action:
Select the column, if possible, in the query that owns the group to which it should be moved.

REP-00507
The file name is invalid.

Category:
Other

Cause:
In a file selection dialog box, the dialog box was accepted without specifying a file name.

Action:
Enter a name and then accept or cancel the dialog box.

REP-00508
The object name is invalid.

Category:
Other

Cause:
In a database object selection dialog box, the dialog box was accepted without specifying an object name.

Action:
Enter a name and then accept or cancel the dialog box.

REP-00509
The number value is invalid.

Category:
Other

Cause:
In a numeric field, something other than a digit or a decimal point was entered.

Action:
Enter a number that contains only digits and, if necessary, a decimal point.

REP-00510
The Unit of Measurement value is invalid.

Category:
Other

Cause:
An invalid unit of measurement was entered in the Unit of Measurement field.

Action:
Select the desired option from the list of values: 'Character', 'Inch', 'Centimeter' or 'Point'

REP-00511
The Panel Print Order value is invalid.

Category:
Other

Cause:
The Panel Print Order entered was not one of the two valid options.

Action:
Select the desired option from the list of values: 'Across/Down' or 'Down/Across'.

REP-00512
The number value is invalid.

Category:
Other

Cause:
The number entered was a decimal value and Oracle Reports Builder was expecting a non-decimal value.

Action:
Enter a non-decimal value.

REP-00513
The Unit of Measurement value is invalid.

Category:
Other

Cause:
The Unit of Measurement is blank and an attempt was made to move to another setting.

Action:
Select an option for Unit of Measurement.

REP-00514
The Page Size value is invalid.

Category:
Other

Cause:
The Page Width and/or Page Height settings were left blank and they require a value.

Action:
Enter a number for Page Width and/or Page Height.

REP-00515
The Parameter Form Size value is invalid.

Category:
Other

Cause:
The Parameter Form Width and/or Parameter Form Height settings were left blank and they require a value.

Action:
Enter a number for Parameter Form Width and/or Parameter Form Height.

REP-00516
The Page Size value is invalid.

Category:
Other

Cause:
The value entered for Page Size was not in character units, and Page Size requires character units.

Action:
Enter a value in characters for Page Size.

REP-00517
The Form Size value is invalid.

Category:
Other

Cause:
The value entered for Form Size was not in character units, and Form Size requires character units.

Action:
Enter a value in characters for Form Size.

REP-00518
The Object Access value is invalid.

Category:
Other

Cause:
The Object Access setting entered was not one of the three valid choices.

Action:
Select an option from the list of values: Database, File, or File/Database.

REP-00519
The Default Text Edit Mode value is invalid.

Category:
Other

Cause:
The Default Text Edit Mode entered was not one of the two valid choices.

Action:
Select an option from the list of values: Insert or Replace.

REP-00520
The Group/Frame Indentation value is invalid.

Category:
Other

Cause:
The value entered for Group/Frame Indentation was outside the valid range of values.

Action:
Enter a number between 0 and 4.

REP-00521
The name {0} is not valid.

Category:
Other

Cause:
An object was given an invalid name.

Action:
Verify the naming conventions for the object type.

REP-00522
A default layout cannot be built because this report has no groups.

Category:
Other

Cause:
Insert>Report Block was selected or a region was drawn using the Report Block tool in the Paper Layout editor before creating a query. A data source is required in order to create a default layout.

Action:
Create one or more queries, then retry the operation.

REP-00523
The Default Layout Style is invalid.

Category:
Other

Cause:
The Default Layout Style entered is not one of the valid options.

Action:
Select a layout style from the list of values.

REP-00524
The Print Direction is invalid.

Category:
Other

Cause:
The Repeat value entered is not one of the valid options.

Action:
Select a value for Repeat from the list of values.

REP-00525
The destination type is invalid.

Category:
Other

Cause:
The destination type entered for the system parameter DESTYPE is not one of the valid options. Possible causes of this error include the following: Case 1: An invalid value was entered for Destination Type in the Runtime Parameter Form. Case 2: An invalid value was entered for Initial Value in the Parameter Property Inspector for DESTYPE.

Action:
Take the following actions to correct this error: If Case 1: Enter one of the valid values, Screen, File, Printer, Mail, or Sysout. If Case 2: Select a value for Initial Value from the list of the values.

REP-00526
The initial value entered is longer than the parameter width.

Category:
Other

Cause:
The value entered is too long for the parameter on the Parameter Property Inspector. The possible causes of this error include the following: Case 1: The Initial Value entered is too big, given what was specified for the parameter's Width. Case 2: The Width entered is too small to contain the values to be entered for the parameter.

Action:
Take the following actions to correct this error: If Case 1: Reenter the Initial Value, making sure that it is not wider than what is specified in Width. If Case 2: Delete the Initial Value. Move to the Width setting for the parameter and increase it such that it can contain the Initial Value specified. Reenter the Initial Value.

REP-00527
A system parameter cannot be deleted.

Category:
Other

Cause:
An attempt was amde to delete a system parameter from the Parameter Property Inspector. This is not allowed.

Action:
To remove the system parameter from the Runtime Parameter Form, suppress the display of the parameter.

REP-00528
The data type value is invalid.

Category:
Data

Cause:
The value entered in Datatype for the parameter is not a valid data type.

Action:
Select a value for Datatype from the list of values: Character, Number, or Date.

REP-00529
The Type value is invalid.

Category:
Other

Cause:
The value entered in Type for the boilerplate is not a valid type.

Action:
Select a value for Type from the list of values: Box, Graphic, Line, or Text.

REP-00530
The file is too long. It will be truncated to fit.

Category:
Other

Cause:
An attempt was made to import a file into a field that has a maximum width less than the size of the file. Oracle Reports Builder only imported as much of the file as could fit in the field.

Action:
To import the entire file, increase the size of the field.

REP-00531
The Object Type is invalid.

Category:
Other

Cause:
In the Navigate to Object dialog box, the value entered for Object Type was invalid.

Action:
Select a value from the list of values.

REP-00532
There is no object of that type with this name.

Category:
Other

Cause:
The value entered in the Object Name field of the Navigate to Object dialog box does not correspond to an object of the specified type in the report.

Action:
Verify the name and that the object is contained in the current report.

REP-00533
Import is allowed only to a text entry field.

Category:
Other

Cause:
Import was selected from the Edit menu while in a non-text entry field (for example, a field that accepts only a number).

Action:
Move to a text entry field to perform an import operation.

REP-00534
Export is allowed only from a text entry field.

Category:
Other

Cause:
Export was selected from the Edit menu while in a non-text entry field (for example, a field that accepts only a number).

Action:
Move to a text entry field to perform an export operation.

REP-00535
No object named {0} exists in the database.

Category:
Other

Cause:
An attempt was made to perform an operation on a document stored in the database, but Oracle Reports Builder could not find the object.

Action:
Verify the name and connection to the database where the document resides.

REP-00536
An object in the database cannot be deleted without ownership.

Category:
Other

Cause:
An attempt was made to delete an object without ownership privileges.

Action:
Request that the owner delete the object.

REP-00537
An object in the database cannot be renamed without ownership.

Category:
Other

Cause:
An attempt was made to rename an object without ownership privileges.

Action:
Request that the owner rename the object.

REP-00538
An object named {0} already exists in the database.

Category:
Other

Cause:
The name entered for the object is already used for an existing object.

Action:
Provide a different name for the object to avoid the conflict or delete the existing object.

REP-00539
The default Parameter Form cannot fit in {0} pages.

Category:
Other

Cause:
The default Parameter Form is too big to fit on the number of pages allocated.

Action:
In the report's Property Inspector, under Parameter Form Window, set the Number of Pages property to the maximum number of pages that the Parameter Form can span.

REP-00540
The page size is too small for the default Parameter Form.

Category:
Other

Cause:
The current Form Width and Form Height settings are too small for the default Parameter Form.

Action:
Increase the size of the Parameter Form pages in the Report Property Inspector by changing Form Width and Form Height. Alternatively, select Tools>Default Parameter Form to default the Parameter Form and reduce its size by editing it in the Parameter Form editor.

REP-00541
The source must be a report.

Category:
Other

Cause:
For Reports Runtime, Converter, or Tools>File Conversion, something other than a report was specified as the source. These operations all require a report as their source.

Action:
Specify a report as the source for the operation.

REP-00542
No date masks have been specified as preferences.

Category:
Other

Cause:
While in the Parameter or Field Property Inspector of a parameter/field of Type Date, the List button was selected for Input Mask or Format Mask, but no masks are specified in the Date Mask list of the Preferences tab of the Tools Options dialog box.

Action:
Enter a date format mask manually or go to the Preferences tab of the Tools Options dialog box and enter some date format masks in the Date Mask list.

REP-00543
No number masks have been specified as preferences.

Category:
Other

Cause:
While in the Parameter or Field Property Inspector of a parameter/field of Type Number, the List button was selected for Input Mask or Format Mask, but no masks are specified in the Number Mask list of the Preferences tab of the Tools Options dialog box.

Action:
Enter a number format mask manually or go to the Preferences tab of the Tools Options dialog and enter some number format masks in the Number Mask list.

REP-00544
The online help system is not available.

Category:
Other

Cause:
Online help was not found. This may have happened because the help files are not installed or because of a help system error.

Action:
Install Developer Tools during Oracle Fusion Middleware installation to install Oracle Reports Builder, which includes the Oracle Reports Online Help. Or, view the Reports Online Help on the Oracle Technology Network (OTN) at http://www.oracle.com/technology/products/reports/index.html.

REP-00545
The number must be greater than 0.

Category:
Other

Cause:
Zero (0) was entered for Page Width, Page Height, or Logical Page Size in the Report Property Inspector.

Action:
Enter a number greater than zero for Page Width, Page Height, or Logical Page Size.

REP-00546
The parameter value is invalid.

Category:
Other

Cause:
In the Runtime Parameter Form, the parameter value entered was invalid.

Action:
Retry the operation with a valid value for the parameter.

REP-00548
An error occurred initializing Oracle Toolkit.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00549
The DESTYPE value is invalid.

Category:
Other

Cause:
An attempt was made to run a report in the background (that is, BATCH=YES), but DESTYPE specified was invalid for running in the background.

Action:
Change the DESTYPE to File, Printer, Mail, or Sysout, or do not run the report with BATCH=YES.

REP-00550
The parent group name is invalid.

Category:
Other

Cause:
The name entered does not identify a valid parent group in the report being defined.

Action:
Select a group from the list of values.

REP-00551
The parent group column is invalid.

Category:
Other

Cause:
The name entered does not identify a valid parent column in the report being defined. The column specified does not exist in the parent group.

Action:
Select a column from the list of values. If the required column does not appear, add it to the SELECT statement of the parent query of the group specified in Parent Group.

REP-00552
The child column name is invalid.

Category:
Other

Cause:
The name entered does not identify a valid child column in the report being defined. The column specified does not exist in the query.

Action:
Select a column from the list of values. If the required column does not appear, add it to the SELECT statement of the query.

REP-00553
The condition is invalid.

Category:
Other

Cause:
The Condition entered for the query is not one of the valid choices.

Action:
Select a value from the list of values for Condition.

REP-00554
The SQL clause value is invalid.

Category:
Other

Cause:
The value entered in SQL Clause is not one of the valid choices.

Action:
Select a value from the list of values for SQL Clause: WHERE, HAVING, or START WITH.

REP-00555
START WITH is Oracle-specific SQL syntax. The report will not run against a non-Oracle database.

Category:
Other

Cause:
The START WITH clause is only available with the Oracle database, but there is no connection or a non-Oracle database connection.

Action:
Either run the report against an Oracle database or remove the START WITH clause before running it against a non-Oracle database.

REP-00556
No data links are created. No foreign key in the child query {0} refers to a primary key in the parent query {1}.

Category:
Data

Cause:
An attempt was made to create a query-to-query link but no foreign key exists in the child query.

Action:
Verify that the tables are accessible, and add the appropriate column constraints if desired.

REP-00558
The query {0} created the lexical parameter {1}.

Category:
Other

Cause:
The specified query references one or more lexical parameters that did not exist.

Action:
No action is needed. Oracle Reports Builder has already created the necessary lexical parameters.

REP-00559
The query {0} has created the bind parameter {1}.

Category:
Other

Cause:
The specified query references one or more bind parameters that did not exist.

Action:
No action is needed. Oracle Reports Builder has already created the necessary bind parameters.

REP-00560
The group name value is invalid.

Category:
Other

Cause:
The group name entered in Group is not a valid group for the column. The group specified does not exist or cannot own the column.

Action:
Create or modify the group such that it can own the column. A database column must be owned by the group associated with the query that selects it. A summary or formula column must be owned by a group that is below the groups that owns the columns being summarized in the group hierarchy (that is, the order of groups as they appear in the Data Model editor).

REP-00561
The type value is invalid.

Category:
Other

Cause:
The value entered in Type for the column was not one of the valid choices.

Action:
Select a value from the list of values for the column's Type: Formula, Summary, or Placeholder.

REP-00562
The column data type value is invalid.

Category:
Data

Cause:
The value entered in Datatype was not one of the valid choices.

Action:
Select a value from the list of values for Datatype.

REP-00563
The data type value is invalid.

Category:
Data

Cause:
The value entered in Datatype was not one of the valid choices.

Action:
Select a value from the list of values for Datatype: Ascending, Descending, or blank.

REP-00564
The file type value is invalid.

Category:
Other

Cause:
The file type value entered in Read From File was not one of the valid types.

Action:
Select a file type from the list of values for Read from File.

REP-00565
The function value is invalid.

Category:
Other

Cause:
The function entered for Function was not one of the valid choices.

Action:
Select one of the functions from the list of values.

REP-00566
The database column cannot be deleted.

Category:
Other

Cause:
An attempt was made to delete a column with a Type of Database.

Action:
Remove the column from the SELECT list of the query that selects it and the column will be deleted automatically.

REP-00567
The summary source value is invalid.

Category:
Other

Cause:
The column entered in Source for the summary was not one of the valid choices. The possible causes of this error include the following: Case 1: The column does not exist. Case 2: The

data type of the Source is Character or Date. Numeric functions (such as Percent, Sum, or Average) require a data type of Number.

Action:
Take the following actions to correct this error: If Case 1: Select a column from the list of values for the function. If Case 2: Enter the name of another column in Source that is of data type Number.

REP-00568
The Value if Null value is invalid.

Category:
Other

Cause:
The value of Value if Null in the Column Property Inspector is invalid for that column. For example, if data type of the column is Number, and a character string was sepcified in Value if Null.

Action:
Specify a valid value for Value if Null.

REP-00569
The query is not parsable, which invalidates associated data link(s).

Category:
Other

Cause:
The query entered in query dialog is not parsable.

Action:
Modify the query and re-create data link(s).

REP-00580
The filter type value is invalid.

Category:
Other

Cause:
The value entered for Type under Filter was not one of the valid choices.

Action:
Select one of the filter types from the list of values.

REP-00581
This is the only group of query {0}, and may not be deleted.

Category:
Other

Cause:
An attempt was made to delete a group that is the only one of the query. Each query must have at least one group.

Action:
To delete the group, delete the group's query.

REP-00582
A group cannot be moved out of its query.

Category:
Other

Cause:
An attempt was made to move a group between queries. Groups can only be moved within the set of groups belonging to the same query.

Action:
Create a group similar to the one that was attempt to be moved under the other query, if possible.

REP-00583
The SQL SELECT Statement is invalid.

Category:
Other

Cause:
The SQL SELECT statement entered was not valid.

Action:
Check the SELECT statement for errors and correct them. For more information, see the SQL Language Reference Manual.

REP-00584
Lexical parameters are not permitted in external queries.

Category:
Other

Cause:
A lexical reference was made in an external query. This is not allowed.

Action:
Delete the reference altogether or, if possible, change it to a bind reference.

REP-00585
The arent group {0} for child query {1} does not exist.

Category:
Other

Cause:
A query was deleted without deleting references to its groups in data links. This usually happens when a query is deleted without cascading the deletion to its associated objects.

Action:
Update the data link in the child query.

REP-00586
Adding this data link will create a cycle.

Category:
Data

Cause:
The group specified as the parent group for the data link is not eligible to be a parent because it is, directly or indirectly, a child of the query to which it is linked.

Action:
If possible, move the group such that it is not a child of the query and therefore eligible to be its parent group.

REP-00587
The PL/SQL group filter condition value is invalid.

Category:
Other

Cause:
Condition was selected for Filter Type, but no PL/SQL condition was entered.

Action:
Enter the PL/SQL or change the Filter Type.

REP-00588
The PL/SQL column formula value is invalid.

Category:
Other

Cause:
Formula was selected as the column's Type, but no PL/SQL for the formula was entered.

Action:
Create a formula or change the column's Type.

REP-00590
Only {0} pages were formatted. The last page is shown.

Category:
Other

Cause:
In the Previewer, an attempt was made to go to a page number that is larger than the total number of pages formatted.

Action:
No action is needed. Do not attempt scroll down from the last page of the report.

REP-00591
The first page is already shown.

Category:
Other

Cause:
In the Previewer, First was selected on the first page of the report.

Action:
No action is needed. Do not attempt to scroll up from the first page of the report.

REP-00592
The last page is already show.

Category:
Other

Cause:
In the Previewer, Last was selected on the last page of the report.

Action:
No action is needed. Do not attempt to scroll down from the last page of the report.

REP-00593
Page {0} is the current page.

Category:
Other

Cause:
In the Previewer, the page number of the current page was entered.

Action:
Enter a different page number and select Go To.

REP-00594
No report output is generated.

Category:
Other

Cause:
The report generated no output.

Action:
Check the accompanying messages for errors in the data model and layout. If the problem persists, contact Oracle Support Services for assistance.

REP-00595
The report definition was modified. Rerunning report.

Category:
Other

Cause:
A report was run and while its output was still in the Previewer, the report definition was modified. The report is rerun to reflect the most recent changes

Action:
Save the changes, close the Previewer, and run the report again.

REP-00596
A page number cannot be greater than {0} or less than 1.

Category:
Other

Cause:
An invalid value was entered for the Page Number setting on the Field Property Inspector for a Parameter Form field. The most likely cause is that values entered were zero, a negative number, or a number that is larger than the largest allowable value.

Action:
Enter a number within the range shown in the message.

REP-00597
This operation is invalid, since it moves objects out of bounds.

Category:
Other

Cause:
An attempt was made to move editor objects in such a way that they would be off the screen.

Action:
Retry the operation so that it will not move objects off the screen.

REP-00598
The anchor end point is out of the boundary of the object.

Category:
Other

Cause:
In moving an anchor, the end point was moved off of the boundary of the object it anchors.

Action:
Move the anchor such that its endpoint is still on the boundary of the object.

REP-00599
This text boilerplate is not editable.

Category:
Other

Cause:
An attempt was made to edit the text of a file link text boilerplate object while it was displayed in the Paper Layout view.

Action:
To edit the text of a file link text boilerplate object, exit the report and edit the file containing the boilerplate text using a text editor.

REP-00600
No list of values is available for this field.

Category:
Other

Cause:
An attempt was made to access a list of values for the current field when none is available.

Action:
No action necessary.

REP-00601
The list of values for this field is empty.

Category:
Other

Cause:
An attempt was made to select from a list of values and the list of values has no values. In order for some lists of values to contain values, another part of the report must be built first. For example, if a list of values is made up solely of column names and the data model is not complete, this error may display.

Action:
Build the report fully. If the error persists, contact Oracle Support Services.

REP-00602
The accessible tables cannot be queried.

Category:
Other

Cause:
The dictionary view of accessible tables is not present or not available.

Action:
See the system administrator.

REP-00603
Table {0} cannot be described.

Category:
Other

Cause:
The dictionary view of accessible tables is not present or not available.

Action:
See the system administrator.

REP-00604
The SELECT statement cannot be built.

Category:
Other

Cause:
The Table and Columns Names dialog box was accepted without anything selected with which to build the SELECT statement.

Action:
Select a table and, if desired, columns or the SELECT columns FROM table option, and then accept the dialog box. To exit the dialog box without building a SELECT statement, click Close.

REP-00606
Link file {0} cannot be read.

Category:
Other

Cause:
Case 1: The file specified in the Source Filename property for the file link boilerplate object cannot be found or its format does not match that specified in the File Format property. Case 2: The REPORTS_DEFAULT_DISPLAY environment variable is set to YES and the image format used is not supported.

Action:
Take the following actions to correct this error: If Case 1: Verify that the file is stored in the specified directory under the specified name, and that it is saved in the specified format. If it is not, change the directory, file name, or format as appropriate. If Case 2: Verify that the image format is one of the supported formats: GIF, JPEG, JPG, PNG, BMP.

REP-00607
Run-only file {0} may not be opened.

Category:
Other

Cause:
An attempt was made to open a runfile (extension .rep). Runfiles cannot be opened, they can only be executed.

Action:
Open the report definition that is associated with the .rep file. It should have an extension of .rdf.

REP-00608
The Source Type is invalid.

Category:
Other

Cause:
Convert was selected from the File menu and the Source Type specified is not valid.

Action:
Select a valid Source Type from the list of values.

REP-00609
The Destination Type is invalid.

Category:
Other

Cause:
Convert was selected from the File menu and the Destination Type specified is not valid.

Action:
Select the Destination Type from the list of values.

REP-00610
An error occurred while attempting to print the screen. Verify that log file {0} is accessible.

Category:
Other

Cause:
Oracle Reports Builder attempted to write the contents of the screen to the file printdef.dat but could not locate the file.

Action:
To determine the proper location for printdef.dat, see the installation instructions.

REP-00611
The Destination Type value is not valid.

Category:
Other

Cause:
In the Runtime Parameter Form, the value provided for Destination Type that was not valid.

Action:
Specify a value of Screen, File, Printer, or Mail for Destination Type.

REP-00612
The date mask value is invalid.

Category:
Other

Cause:
The date mask entered does not correspond to any of the valid date masks.

Action:
Verify the date mask format. For more information, see the date and time format mask information in the Building Reports manual.

REP-00613
The Format Mask value does not match mask {0}.

Category:
Other

Cause:
The mask entered in Format Mask is not a valid mask. The possible causes of this error include the following: Case 1: The string entered as a mask contained invalid characters. Case 2: A number format mask was entered for a field with data type of Character.

Action:
Take the following actions to correct this error: If Case 1: Select a value from the list of values. For more information, see the date and time format mask information in the Building Reports manual. If Case 2: Change the data type of the field to be Number, if possible. If the field is supposed to be Character data type and cannot be changed, a format mask cannot be specified for it.

REP-00614
There is no window active for the Find and Replace action.

Category:
Other

Cause:
A Find and Replace operation was attempted using the Find And Replace dialog box, but the cursor was not positioned in an active Oracle Reports Builder window.

Action:
Position the cursor in a text entry field before performing a Find and Replace operation.

REP-00615
Find and Replace is valid only for a text entry field.

Category:
Other

Cause:
A Find and Replace operation was attempted using the Find And Replace dialog box, but the cursor was not positioned positioned in a text entry field. Find and Replace operations are valid only in text entry fields.

Action:
Position the cursor in a entry field before performing a Find and Replace operation.

REP-00616
Text cannot be replaced in an uneditable region.

Category:
Other

Cause:
Using the Find And Replace dialog box, text replacement was attempted in an inaccessible field.

Action:
Replace text only in editable regions.

REP-00617
The Runtime Parameter Form is already open. To run a new one, close the old one and run again.

Category:
Other

Cause:
An attempt was made to run a report with the Runtime Parameter Form already open.

Action:
Close the currently open Runtime Parameter Form and try running again.

REP-00619
A report cannot be run without a layout.

Category:
Other

Cause:
An attempt was made to run the report with no layout.

Action:
Create a layout, then run the report.

REP-00621
The Vertical Elasticity value is invalid.

Category:
Other

Cause:
The value entered for the object's Vertical Elasticity was not one of the valid values.

Action:
Select a value from the list of values.

REP-00622
The Horizontal Elasticity value is invalid.

Category:
Other

Cause:
The value entered for the object's Horizontal Elasticity was not one of the valid values.

Action:
Select a value from the list of values.

REP-00623
The Print Condition Type value is invalid.

Category:
Other

Cause:
The value entered for the Type of the Print Condition was not one of the valid values.

Action:
Select a value from the list of values.

REP-00624
The Print Condition Object value is invalid.

Category:
Other

Cause:
The value entered for the Object of the Print Condition was not one of the valid values.

Action:
Select a value from the list of values.

REP-00625
The Text Alignment value is invalid.

Category:
Other

Cause:
The value entered for Alignment was not one of the valid values. The value is not valid given the data type of the object. Flush/Left, Flush/Center, and Flush/Right are only valid for fields with data type of Character.

Action:
Select a value from the list of values.

REP-00626
The coordinate position value is invalid.

Category:
Other

Cause:
The x or y coordinate entered was not in the valid range for coordinates. Coordinates cannot be negative numbers.

Action:
Enter a coordinate that is in the valid range.

REP-00627
The object height or width must be a positive integer.

Category:
Other

Cause:
The Width or Height value entered was not a positive, whole number.

Action:
Enter a positive, whole number.

REP-00630
The value must be between {0} and {1}.

Category:
Other

Cause:
The number entered was too large or too small.

Action:
Specify a number that is within the range shown in the message.

REP-00631
The string must be no longer than {0} characters.

Category:
Other

Cause:
The string entered was too large.

Action:
Enter a string that is smaller than the number of characters shown in the message.

REP-00632
The value already exists in the list.

Category:
Other

Cause:
An attempt was made to add an item to a list, but the item was previously added to the list. For example, if an attempt was made to add lib1 to the report's Attached PL/SQL Library list, when lib1 was already found in the Attached PL/SQL Library list, this error displays.

Action:
Once an item has been added to a list, do not attempt to add it again.

REP-00633
No value is specified.

Category:
Other

Cause:
An attempt was made to perform a list operation on an item, but no item was specified. For example, if an attempt was made to add a PL/SQL library to the report's Attached PL/SQL Library list, but the PL/SQL Library field in the Attached PL/SQL Libraries dialog box was left blank and the Add button selected, this error displays.

Action:
Specify the item to add in the appropriate field before choosing a button.

REP-00634
The destination name must be shorter than {0} characters.

Category:
Other

Cause:
The destination specified (probably a file name) was too long.

Action:
Specify a destination that it is of valid length.

REP-00635
The value does not exist in the list.

Category:
Other

Cause:
The value specified was not in the list of valid choices.

Action:
Specify one of the valid choices in the list. If possible, use the list of values to ensure that it is a valid choice.

REP-00636
Property name {0} must be no longer than {1} characters. It will be truncated.

Category:
Other

Cause:
The string specified was longer than is allowable. It will be truncated.

Action:
Specify a shorter string.

REP-00637
Property name {0} must be no longer than {1} characters.

Category:
Other

Cause:
The file name specified was longer than is allowable.

Action:
Specify a shorter file name.

REP-00639
Set a valid DISPLAY value when REPORTS_DEFAULT_DISPLAY is set to NO.

Category:
Other

Cause:
REPORTS_DEFAULT_DISPLAY was set to NO and DISPLAY variable was not set.

Action:
Specify a valid value for DISPLAY when REPORTS_DEFAULT_DISPLAY is set to NO.

REP-00640
The field source value is invalid.

Category:
Other

Cause:
The Source value specified was invalid.

Action:
Select a value from the list of values.

REP-00650
The source group value is invalid.

Category:
Other

Cause:
The group name specified in Source for the repeating frame was invalid.

Action:
Select a value from the list of values.

REP-00651
The Print Direction value is invalid.

Category:
Other

Cause:
The Print Direction specified was not one of the valid values (Across, Across/Down, Down, Down/Across, and Matrix Cell).

Action:
Select a value from the list of values.

REP-00652
The Vertical Spacing value is invalid.

Category:
Other

Cause:
The Vertical Spacing specified was not a valid value.

Action:
Enter zero or a positive integer for Vertical Spacing.

REP-00653
The Horizontal Spacing value is invalid.

Category:
Other

Cause:
The Horizontal Spacing specified was not a valid value.

Action:
Enter zero or a positive integer for Horizontal Spacing.

REP-00654
The Maximum Records per Page value is invalid.

Category:
Other

Cause:
The Maximum Records per Page specified was not a valid value.

Action:
Enter blank or a positive integer for Maximum Records per Page.

REP-00655
The Minimum Widow Records value is invalid.

Category:
Other

Cause:
The Minimum Widow Records specified was not a valid value.

Action:
Enter blank or a positive integer for Minimum Widow Records.

REP-00660
The button source value is invalid.

Category:
Other

Cause:
Multimedia Column was selected as the source for the button action, but the source column was either not specified or invalid.

Action:
Specify a valid source column for the button action, containing sounds, video, or images.

REP-00661
The button source value is invalid.

Category:
Other

Cause:
Multimedia File was selected as the source for the button action, but the source file was either not specified or invalid.

Action:
Specify a valid source file for the button action, containing sounds, video, or images.

REP-00662
The button icon value is invalid.

Category:
Other

Cause:
Icon was selected as the button face, but the icon name was invalid.

Action:
Enter the name of a valid icon file in the text field provided. Include all necessary path information.

REP-00670
The boilerplate type value is invalid.

Category:
Other

Cause:
The Type specified for the boilerplate was not one of the valid values.

Action:
Select a Type from the list of values: Box, Line, Graphic, and Text.

REP-00671
The link file name value is invalid.

Category:
Other

Cause:
The file to which the file link boilerplate object was linked is not a valid file.

Action:
In the Property Inspector for the File Link boilerplate object, check that the Source Filename property is set to an existing file in the current directory.

REP-00672
The Minimum Widow Lines value is invalid.

Category:
Other

Cause:
The Minimum Widow Lines specified was not a valid value.

Action:
Enter blank or a positive integer for Minimum Widow Lines.

REP-00680
The anchoring object name value is invalid.

Category:
Other

Cause:
The object name entered in the Anchored To field of the Anchor Position dialog box was not the name of an object to which this object can be anchored.

Action:
Select an object name for Anchored To from the list of values.

REP-00681
The Edge value is invalid.

Category:
Other

Cause:
The Edge specified was not one of the valid values (Top, Left, Right, and Bottom).

Action:
Select a value for Parent Edge or Object Edge from the list of values.

REP-00682
The anchor point must be a percentage between 0 and 100.

Category:
Other

Cause:
The % specified was not in the valid range (0 to 100).

Action:
Enter a value in the valid range for %.

REP-00690
The starting page number value is invalid.

Category:
Other

Cause:
Start At was left blank.

Action:
Enter zero or a positive integer for Start At.

REP-00691
The page increment value is invalid.

Category:
Other

Cause:
Increment By was blank.

Action:
Enter zero or a positive whole number for Increment By.

REP-00692
The page number reset value is invalid.

Category:
Other

Cause:
Reset At was left blank.

Action:
Select a repeating frame name or &Report from the list of values to indicate where to reset the page number to its Start At value.

REP-00700
The color value is invalid.

Category:
Other

Cause:
The color specified was not one of the valid choices.

Action:
Select a color for the field from the list of values.

REP-00701
The pattern value is invalid.

Category:
Other

Cause:
The pattern specified was not one of the valid choices.

Action:
Select a pattern for the field from the list of values.

REP-00702
The pen width value is invalid.

Category:
Other

Cause:
The pen width specified was not one of the valid choices.

Action:
Select a pen width from the list of values.

REP-00703
The font value is invalid.

Category:
Other

Cause:
The font specified was not one of the valid choices.

Action:
Select a font from the list of values.

REP-00704
The text style value is invalid.

Category:
Other

Cause:
The text style specified was not one of the valid styles.

Action:
Select one of the styles from the list of values.

REP-00705
The text weight value is invalid.

Category:
Other

Cause:
The text weight specified was not one of the valid weights.

Action:
Select one of the weights from the list of values.

REP-00706
The text size value is invalid.

Category:
Other

Cause:
The point size specified was not one of the valid choices.

Action:
Select a valid point size from the list of values.

REP-00707
The text spacing value is invalid.

Category:
Other

Cause:
The spacing value specified was not in the valid range.

Action:
Enter a number in the valid range.

REP-00708
The character mode attribute value is invalid.

Category:
Other

Cause:
The character mode attribute specified was not valid. The values specified in Character Mode Attribute must be defined in the printer definition. To have these attributes appear in the list of values, they must also be listed in VISUAL_PREFS in the preferences file.

Action:
Select the desired values from the list of values. If the desired value is not in the list of values, check the printer definition to verify if the value is a valid one.

REP-00709
Sysout is only valid in batch mode.

Category:
Other

Cause:
Sysout was specified as the destination type when not running the report in batch mode. The possible causes of this error include the following: Case 1: Sysout was specified for DESTYPE in the Runtime Parameter Form. Case 2: Sysout was specified as the Initial Value for DESTYPE and was accepted when not running in batch mode. This may occur inadvertently when the Hide Parameter Form preference is checked.

Action:
Take the following actions to correct this error: If Case 1: Run the report again, but enter a DESTYPE of something other than Sysout unless running in batch mode. If Case 2: Change the Initial Value for DESTYPE to something else or change the DESTYPE to something other than Sysout in the Runtime Parameter Form. If the Initial Value is left as Sysout, do not run in non-batch mode with Hide Parameter Form checked.

REP-00710
The printer description file cannot be found.

Category:
Other

Cause:
Oracle Reports Builder could not find the printer description file specified for DESFORMAT.

Action:
Specify a valid printer description file for DESFORMAT (for example, dflt).

REP-00711
The destination type must be File, Printer, or Mail when printing from the Previewer.

Category:
Other

Cause:
The Print button was selected in the Previewer, but DESTYPE was restricted to a value other than File, Printer, or Mail.

Action:
Ensure that DESTYPE can be set to one of the valid values before attempting to print from the Previewer.

REP-00712
No printer is specified.

Category:
Other

Cause:
An attempt was made to print a report, without a printer name specified in either DESNAME or in the Printer Chooser dialog box.

Action:
Specify a valid printer name using DESNAME. If the same printer is often used, enter the printer name in the Printer Chooser dialog box. Remember that entering a printer name using DESFORMAT will override the printer name set in the Printer Chooser dialog box.

REP-00713
The printer name {0} specified by parameter {1} is invalid.

Category:
Other

Cause:
An attempt was made to generate a report, without a valid printer name specified in DESFORMAT (if DESTYPE was File or Mail) or DESNAME (if DESTYPE was Printer).

Action:
Specify a valid printer name for DESFORMAT if DESTYPE was File or Mail, or a valid printer name for DESNAME if DESTYPE was Printer.

REP-00714
The mail destination value is invalid.

Category:
Other

Cause:
An attempt was made to mail report output to another user, but did not specify a valid username for DESNAME.

Action:
Specify a valid username for DESNAME.

REP-00715
A trace file must be specified when tracing.

Category:
Other

Cause:
Trace mode or trace options were specified without specifying a trace file.

Action:
Specify a trace file.

REP-00716
The option specified for tracing is invalid.

Category:
Other

Cause:
Invalid trace options were specified.

Action:
Respecify trace options. For more information about trace options, see the Publishing Reports to the Web manual.

REP-00717
Options cannot be set or unset if not tracing.

Category:
Other

Cause:
An attempt was made to set or unset trace options while not tracing.

Action:
Begin tracing before attempting to set or unset options.

REP-00718
Trace break information cannot be traced with Reports Runtime.

Category:
Other

Cause:
An attempt was made to trace breaks while running the report using Reports Runtime.

Action:
Do not specify the Break option when using Reports Runtime.

REP-00719
Trace file {0} can be written to.

Category:
Other

Cause:
A trace file was specified that does not have write permission.

Action:
Verify the trace file name is valid.

REP-00720
The repeating frame value is invalid.

Category:
Other

Cause:
The repeating frame specified as the Vertical or Horizontal Frame in the Matrix Property Inspector is not valid.

Action:
Select a repeating frame name from the list of values.

REP-00721
The cross product group value is invalid.

Category:
Other

Cause:
The group entered for Cross Product Group in the Matrix Property Inspector is not valid.

Action:
Select a group name from the list of values.

REP-00723
Uncompiled program units exist, possibly due to no connection to the database.

Category:
Other

Cause:
An attempt was made to convert a report or load an old report, containing PL/SQL which needed to be recompiled.

Action:
Load the report using Oracle Reports Builder, connect to database, and recompile the DE program units.

REP-00724
The value of column {0} cannot be retrieved.

Category:
Other

Cause:
An attempt was made to get the value of the specified column by either issuing a command from the command line of the PL/SQL Interpreter or by executing a stand-alone PL/SQL program unit. A column value can only be retrieved during report execution.

Action:
Do not attempt to use the PL/SQL Interpreter or a PL/SQL program unit to get the value of a column when the report has suspended execution (for example, at a breakpoint). Use an alternate method, such as one of the report-level triggers, to obtain the column value.

REP-00725
The value of column {0} cannot be set.

Category:
Other

Cause:
An attempt was made to set the value of the specified column by either issuing a command from the command line of the PL/SQL Interpreter or by executing a stand-alone PL/SQL program unit. A column value can only be set during report execution.

Action:
Do not attempt to use the PL/SQL Interpreter or a PL/SQL program unit to set the value of a column when the report has suspended execution (for example, at a breakpoint). Use an alternate method, such as one of the report-level triggers, to set the column value.

REP-00726
The value of parameter {0} cannot be retrieved.

Category:
Other

Cause:
An attempt was made to get the value of the specified parameter by either issuing a command from the command line of the PL/SQL Interpreter or by executing a stand-alone PL/SQL program unit. A parameter value can only be retrieved during Parameter Form execution.

Action:
Do not attempt to use the PL/SQL Interpreter or a PL/SQL program unit to get the value of a parameter when the report has suspended execution (for example, at a breakpoint). Use an alternate method, such as one of the report-level triggers, to obtain the parameter value.

REP-00727
The value of parameter {0} cannot be set.

Category:
Other

Cause:
An attempt was made to set the value of the specified parameter by either issuing a command from the command line of the PL/SQL Interpreter or by executing a stand-alone PL/SQL program unit. A parameter value can only be set during Parameter Form execution.

Action:
Do not attempt to use the PL/SQL Interpreter or a PL/SQL program unit to set the value of a parameter when the report has suspended execution (for example, at a breakpoint). Use an alternate method, such as one of the report-level triggers, to set the parameter value.

REP-00728
Column {0} may not be referenced by parameter triggers.

Category:
Other

Cause:
An attempt was made to reference a column in a parameter-related trigger (Before Form, After Form, Validation), which is not allowed.

Action:
Remove the references from the parameter-related triggers and add them to the Before Report trigger.

REP-00729
The program unit {0} of size {1} bytes is too big to be loaded for the current platform at the limit of {2}.

Category:
Other

Cause:
The program unit was created on another operating platform and it too large to be loaded into the current operating platform.

Action:
Reduce the size of the PL/SQL program unit.

REP-00730
The bind variable is not defined.

Category:
Other

Cause:
A bind reference was made to a parameter or column that has not been defined yet.

Action:
Create the parameter definition or column before making a bind reference to it. Or, attempt to use a lexical reference rather than a bind reference.

REP-00732
An error occurred destroying the program unit.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00733
The specified name already exists.

Category:
Other

Cause:
An attempt was made to create a PL/SQL subprogram whose name is identical to an existing subprogram stored in the report.

Action:
Rename the new subprogram so that it does not conflict with any existing subprograms.

REP-00734
No argument is allowed.

Category:
Other

Cause:
The PL/SQL function or procedure entered requires arguments in a PL/SQL field that does not allow PL/SQL with arguments--for example, in a Format Trigger field, a Formula field, or as a group filter.

Action:
Remove the arguments from the PL/SQL source.

REP-00735
Program unit cannot be loaded.

Category:
Other

Cause:
Oracle Reports Builder could not load the entire program unit. It could be that the program unit references one or more objects stored in the database, but these objects were not found.

Action:
Verify the connection to the correct database, and ensure that the program unit is making the correct references.

REP-00736
Uncompiled program units exist.

Category:
Other

Cause:
An attempt was made to convert a report, or load an old report, containing PL/SQL that needed to be recompiled.

Action:
Load the report using Oracle Reports Builder and modify the program units.

REP-00737
The return type {0} is invalid.

Category:
Other

Cause:
The PL/SQL entered does not have the appropriate return type.

Action:
Change the return type of the function to the one specified in the message.

REP-00738
A function is required.

Category:
Other

Cause:
Something other than a function was entered where a function is required.

Action:
Enter a function.

REP-00739
Compiled PL/SQL from other platform cannot be executed.

Category:
Other

Cause:
An attempt was made to run a report on a platform that is not the same as the platform on which the PL/SQL in the report was compiled. The report does not contain the PL/SQL source and, as a result, Oracle Reports Builder could not recompile the PL/SQL on the current platform.

Action:
Run the report on the original platform where the PL/SQL was compiled. Alternatively, obtain a copy of the source report with the source PL/SQL and recompile it from the current platform.

REP-00740
An anchor cannot be anchored with another object.

Category:
Other

Cause:
An attempt was made to anchor an anchor to another layout object, or anchor a layout object to an anchor.

Action:
Remove any anchors of anchors with other layout objects.

REP-00741
A matrix cannot be anchored with another object.

Category:
Other

Cause:
An attempt was made to anchor a matrix object to another layout object, or anchor a layout object to a matrix object.

Action:
Remove any anchors of matrix objects with other layout objects.

REP-00742
A margin cannot be anchored with another object.

Category:
Other

Cause:
An attempt was made to anchor the margin to a layout object, or anchor a layout object to the margin.

Action:
Remove any anchors of the margin to layout objects.

REP-00743
A matrix repeating frame cannot be anchored with another object.

Category:
Other

Cause:
An attempt was made to anchor a matrix repeating frame with a Print Direction of Down or Across to another layout object.

Action:
Remove any anchors of matrix repeating frames with Print Directions of Down or Across to other layout objects.

REP-00744
An anchor must have different parent and child objects.

Category:
Other

Cause:
An attempt was made to create an anchor whose parent and child objects are the same; that is, anchor an object to itself.

Action:
Ensure that all anchors have different parent and child objects.

REP-00745
An object cannot be anchored more than once.

Category:
Other

Cause:
An attempt was made to create two anchors between the same two layout objects.

Action:
Ensure that only one anchor exists between the same two layout objects.

REP-00746
The PL/SQL references an object that does not exist.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00747
A Before Form trigger cannot reference a report column.

Category:
Other

Cause:
The Before Form trigger for the report references a column in the report, which is not allowed.

Action:
Remove any column references from the Before Form trigger. To set the value of a column, do it from the Before Report trigger.

REP-00748
A parameter trigger cannot reference a report column.

Category:
Other

Cause:
A Validation trigger for a parameter references one or more columns in the report, which is not allowed.

Action:
Remove any column references in the Validation trigger of the Parameter Property Inspector.

REP-00749
An After Form trigger cannot reference a report column.

Category:
Other

Cause:
The After Form trigger for the report references a column in the report, which is not allowed.

Action:
Remove any column references in the After Form trigger. To set the value of a column, do it from the Before Report trigger.

REP-00750
An error occurred closing the PL/SQL library.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00751
An error occurred accessing program units from PL/SQL library.

Category:
Other

Cause:
An abnormal condition was encountered. To save changes made to the PL/SQL library, consider saving it under a different name.

Action:
For assistance, contact Oracle Support Services.

REP-00752
The PL/SQL library cannot be saved.

Category:
Other

Cause:
An abnormal condition was encountered. To save changes made to the PL/SQL library, consider saving it under a different name.

Action:
For assistance, contact Oracle Support Services.

REP-00753
An error occurred attaching PL/SQL library {0}.

Category:
Other

Cause:
An attempt was made to attach an invalid PL/SQL library. This could happen because the PL/SQL library is corrupted, or because the file or object specified does not contain a PL/SQL library.

Action:
Verify that the file or object specified contains a valid PL/SQL library.

REP-00754
An error occurred inserting program units into a PL/SQL library.

Category:
Other

Cause:
An attempt was made to save a program unit into a corrupted PL/SQL library, or a file or object that is not a PL/SQL library.

Action:
Verify the file or object specified contains a valid PL/SQL library and consider saving the current program unit.

REP-00755
An error occurred opening PL/SQL library {0}.

Category:
Other

Cause:
An attempt was made to open a corrupted PL/SQL library, or a file or object that is not a PL/SQL library.

Action:
Verify that the file or object contains a valid PL/SQL library.

REP-00756
PL/SQL library {0} cannot be found.

Category:
Other

Cause:
An attempt was made to attach a PL/SQL library that does not exist, or to open a report with one or more attached PL/SQL libraries that were not found.

Action:
Verify that the file or object exists. If the object is a report, reattach the PL/SQL library.

REP-00757
The external location spec cannot be created.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00758
PL/SQL library {0} is already in use.

Category:
Other

Cause:
An attempt was made to attach a PL/SQL library that has the same name as another PL/SQL library that is already attached. This could happen if a file was renamed that contains a PL/SQL library, but the internal name recognized by Oracle Reports Builder was not changed.

Action:
Save the PL/SQL library under a different name.

REP-00759
One or more PL/SQL libraries have been modified since the report was saved; the PL/SQL will be recompiled.

Category:
Other

Cause:
An attempt was made to open or run a report that references one or more PL/SQL libraries, and part or all of the PL/SQL has been modified but not compiled since the report was last saved.

Action:
No action is necessary; Oracle Reports Builder will recompile the PL/SQL.

REP-00760
A print document session is currently in process.

Category:
Other

Cause:
From the File menu, Administration Report was already selected to produce a report on one or more reports.

Action:
Finish producing the current report on reports, then try again to run another report on reports.

REP-00761
The resource for printing the report cannot be opened.

Category:
Other

Cause:
Oracle Reports Builder cannot open the reports that document other reports for printing.

Action:
Verify that the reports that document other reports (shipped with Oracle Reports Builder) are located in the proper directory. For details on the exact location of these reports, see the installation instructions.

REP-00762
The user ID for the interoffice login is invalid.

Category:
Other

Cause:
An attempt was made to save report output to the interoffice repository, but a valid connect string was not specified for the interoffice document server.

Action:
Specify a valid connect string for the interoffice document server.

REP-00763
The interoffice client {0} cannot be launched.

Category:
Other

Cause:
An attempt was made to launch the interoffice client, but it failed to run.

Action:
Verify that the interoffice client is properly installed.

REP-00764
Error {0} occurred running the interoffice client.

Category:
Other

Cause:
The interoffice client was running to check in the documents into repository, but it failed on the indicated error code.

Action:
Check the interoffice error code/message for the reason of failure.

REP-00769
Sending to mail from the Parameter Form when the Paper Design view is open is invalid.

Category:
Other

Cause:
The Paper Design is open and destype is set to mail.

Action:
Select mail directly from the Paper Design view and not from the Parameter Form.

REP-00770
The Before Form trigger failed.

Category:
Other

Cause:
The Before Form trigger in the report returned false.

Action:
Make the appropriate changes (either to the PL/SQL source in the Before Form trigger or to the report) to make the trigger return true.

REP-00771
The After Form trigger failed.

Category:
Other

Cause:
The After Form trigger in the report returned false.

Action:
Make the appropriate changes (either to the PL/SQL source in the After Form trigger or to the report) to make the trigger return true.

REP-00772
Parameter Form Fields {0} and {1} may not have the same Source.

Category:
Other

Cause:
The same Source was specified for two Parameter Form fields. Fields on the Runtime Parameter Form must have unique sources.

Action:
Change the Source of one of the fields.

REP-00773
No Source was specified for Parameter Form Field {0}.

Category:
Other

Cause:
A Source was not specified for a Parameter Form field or the source parameter was deleted from the data model. Fields on the Runtime Parameter Form must have a source.

Action:
Specify a valid Source for the Parameter Form field.

REP-00774
No selectable values are available for LOV parameter {0}.

Category:
Other

Cause:
Either no values were specified for the LOV parameter's select list, or values were specified that cannot be selected.

Action:
Check the SELECT statement or selectable value list of the parameter to ensure that the specified values are selectable.

REP-00775
The data type of the first column of the SELECT statement does not match the data type of LOV parameter {0}.

Category:
Data

Cause:
The data type of the first column specified in the SELECT statement does not match the data type specified for the LOV parameter.

Action:
Check the data type of the LOV parameter, the SELECT statement, and the columns in the database tables accessed by the SELECT statement to ensure that they match.

REP-00776
There are columns with values in segmented memory when populating LOV parameter {0}. They will be ignored.

Category:
Memory

Cause:
Columns were selected with values in segmented memory for the LOV parameter's select list, which is not allowed.

Action:
Select different columns or move the column values.

REP-00777
There are columns whose types cannot be handled when populating LOV parameter {0}. They will be ignored.

Category:
Other

Cause:
Columns were selected whose types cannot be handled (for example, binary data).

Action:
Select different columns.

REP-00778
Some columns cannot be formatted correctly when populating LOV parameter {0}. They will be ignored.

Category:
Other

Cause:
The SELECT statement selecting values for the parameter's LOV retrieves columns whose values cannot be formatted according to their datatypes.

Action:
Convert the values to valid ones or check the database to see if the values of the columns are valid.

REP-00779
Some items of LOV parameter {0} are too long. These items will be truncated.

Category:
Other

Cause:
The items specified or columns selected contain some values that are too long to include in the LOV parameter's select list.

Action:
Check the values of the items and reduce their length if necessary.

REP-00780
The initial value entered is invalid against the input mask {0}.

Category:
Other

Cause:
The value entered in the Initial Value field violates the mask specified in the Input Mask field.

Action:
Either enter a different value in Initial Value or change the mask in Input Mask.

REP-00781
Bind variables are not allowed in the SELECT statement.

Category:
Other

Cause:
Bbind variables were included in the SELECT statement.

Action:
Remove the bind variables from the SELECT statement.

REP-00782
The data type of the parameter does not match the data type of its source columns.

Category:
Data

Cause:
The column selected has an invalid data type to furnish values for the LOV parameter's select list.

Action:
Change the column's data type or specify a different column.

REP-00783
The possible values list has bad syntax.

Category:
Other

Cause:
Incorrect syntax was specified to create the list of possible values for the LOV parameter.

Action:
Edit the possible values list to ensure that it is a proper comma-separated list.

REP-00784
A possible value has invalid width.

Category:
Other

Cause:
A value specified for the LOV parameter's list of possible values has an invalid width.

Action:
Edit the possible values list so that all possible values have valid widths, or alter the width.

REP-00785
A possible value is invalid against the input mask.

Category:
Other

Cause:
A value specified for the LOV parameter's list of possible values is not formatted in accordance with the specified input mask.

Action:
Edit the possible values list to ensure that all possible values are valid against the input mask.

REP-00786
The initial value is not among the possible values.

Category:
Other

Cause:
The initial value specified for the LOV parameter does not appear on the defined list of possible values.

Action:
Add the initial value specified to the possible values list.

REP-00787
The name of the first column of LOV parameter {0}'s select statement is not the same at runtime as design time.

Category:
Other

Cause:
There is a discrepancy between the columns specified in the original SELECT statement and what the tables in question now contains.

Action:
Check the database to determine if the tables in question have been updated since the parameter list was created, or reapply the LOV parameter's SELECT statement.

REP-00788
The value of restricted LOV parameter {0} is not among the selectable values.

Category:
Other

Cause:
The value specified for a LOV parameter is not on the parameter's select list.

Action:
Select a value from the parameter's select list.

REP-00790
Page Width and Page Height must either both be specified or both be blank.

Category:
Other

Cause:
A blank value was specified for either Page Width or Page Height in the Runtime Settings tab of the Tools Options dialog box.

Action:
Specify a valid value for the blank setting, or make both settings blank.

REP-00800
Select All is valid only in a text entry field.

Category:
Other

Cause:
Select All was selected from the Edit menu with the cursor positioned on an element in the Property Inspector other than a text field.

Action:
While in the Property Inspector, select Edit then Select All only in a text field.

REP-00801
The layout canvas must remain large enough to fit all layout objects.

Category:
Other

Cause:
The painting region of the Paper Layout editor was reduced by changing one or more settings in the Report Properties dialog box, or by resizing the margin, but the resized painting region is not large enough to fit all of the layout objects.

Action:
Verify that all layout objects in the body, margin, header, and trailer sections of the report fit in the resized painting region.

REP-00802
The Parameter Form canvas must remain large enough to fit all Parameter Form objects.

Category:
Other

Cause:
The painting region of the Parameter Form editor was reduced by changing one or more settings in the Report Properties dialog box, but the resized painting region is not large enough to fit all of the Parameter Form objects.

Action:
Verify that all Parameter Form objects fit in the resized painting region.

REP-00803
The canvas size specified is too large.

Category:
Other

Cause:
The report contains combined settings of page/form size and either logical page, maximum body page, maximum header page, maximum footer page, or number of Parameter Form pages that results in a value larger than that supported by Oracle Reports Builder (a dpi value greater than 2 gigabytes).

Action:
Make the page/form size smaller, or decrease the value for logical page size, maximum body pages, maximum header pages, maximum footer pages, or number of Parameter Form pages.

REP-00804
The report definition was modified during the current run. Oracle Reports Builder cannot continue running the Parameter Form or report.

Category:
Other

Cause:
While in the Runtime Parameter Form, the report was modified through an editor or Property Inspector.

Action:
Cancel the Runtime Parameter Form and rerun the report.

REP-00805
Menus cannot be initialized.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00806
An error occurred reading window resources.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-00807
The array size is missing.

Category:
Other

Cause:
In the Runtime Settings dialog box, the Array Size field was left blank.

Action:
Enter an Array Size value between 1 and 9999.

REP-00808
The buffer size is missing.

Category:
Other

Cause:
In the Runtime Settings tab of the Tools Options dialog box, the Buffer Size field was left blank.

Action:
Enter a Buffer Size value between 1 and 9999.

REP-00809
The long chunk size is missing.

Category:
Other

Cause:
In the Runtime Settings tab of the Tools Options dialog box, the Long Chunk Size field was left blank.

Action:
Enter a Long Chunk Size value between 1 and 9999.

REP-00810
The Success/On Failure value is invalid.

Category:
Other

Cause:
In the character-mode Runtime Settings dialog box, On Success/On Failure specified an invalid value.

Action:
Select a valid value for On Success/On Failure: Noaction, Rollback, or Commit.

REP-00811
The Destination Type value is invalid.

Category:
Other

Cause:
In the character-mode Runtime Settings dialog, Destination Type specified an invalid value.

Action:
Select a valid value for Destination Type: <In Report Definition>, Screen, File, Printer, or Mail.

REP-00812
The Orientation value is invalid.

Category:
Other

Cause:
In the character-mode Runtime Settings dialog, Orientation specified an invalid value.

Action:
Select a valid value for Orientation: <In Report Definition>, Landscape, or Portrait.

REP-00813
The Mode value is invalid.

Category:
Other

Cause:
In the character-mode Runtime Settings dialog, Mode specified an invalid value.

Action:
Select a valid value for Mode: <In Report Definition>, Default, Bitmap, or Character.

REP-00814
The Background value is invalid.

Category:
Other

Cause:
In the character-mode Runtime Settings dialog box, Background specified an invalid value.

Action:
Select a valid value for Background: <In Report Definition>, Yes, or No.

REP-00815
The Orientation value is invalid.

Category:
Other

Cause:
In the character-mode Runtime Parameter Form, Orientation specified an invalid value.

Action:
Select a valid value for Orientation: Landscape or Portrait.

REP-00816
The Mode value is invalid.

Category:
Other

Cause:
In the character-mode Runtime Parameter Form, Mode specified an invalid value.

Action:
Select a valid value for Mode: Bitmap or Character.

REP-00817
The Background value is invalid.

Category:
Other

Cause:
In the character-mode Runtime Parameter Form, Background specified an invalid value.

Action:
Select a valid value for Background: Yes or No.

REP-00818
The page height has changed for the Parameter Form. Parameters might be crossed by page boundaries.

Category:
Other

Cause:
The height of the Runtime Parameter Form was changed in the Report Property Inspector. This might cause the page boundary to move such that it appears in the middle of an object in the Parameter Form.

Action:
Examine the layout of the Parameter Form in the Parameter Form editor and ensure that none of the objects are directly on the page boundary (the darkened line in the editor). Alternatively, default (or redefault) the Parameter Form.

REP-00819
AUTOCOMMIT ON for SQL Server connection cannot be set.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services. Another option is to remove all instances of SRW.DO_SQL. If this can be done while retaining all necessary functionality in the report, it will run.

REP-00820
cannot import specified image

Category:
Other

Cause:
The specified image cannot be imported.

Action:
Check the image file to ensure it is a valid image and has not been corrupted.

REP-00821
cannot export specified image

Category:
Other

Cause:
The specified object cannot be exported as an image.

Action:
Create or select an image to export.

REP-00822
no drawing imported

Category:
Other

Cause:
The specified drawing cannot be imported.

Action:
Check the file to ensure it is a valid drawing and has not been corrupted.

REP-00823
no drawing exported

Category:
Other

Cause:
The specified object cannot be exported as a drawing.

Action:
Create or select a drawing to export.

REP-00824
The data dictionary is not available on the connected database.

Category:
Data

Cause:
An attempt was made to access the Table and Column Names dialog box but the Data Dictionary is not available on the connected database.

Action:
Connect to another database.

REP-00825
The connected database is not Oracle or DB2. It cannot be used to store report documents.

Category:
Other

Cause:
An attempt was made to store a document to a database that is neither Oracle nor DB2, which is not allowed.

Action:
Either connect to an Oracle or DB2 database or store the document as a file.

REP-00828
Oracle Reports Builder tables are not installed in the database: cancelling report.

Category:
Other

Cause:
The report cannot be run because there are no Oracle Reports Builder tables in the database.

Action:
Inform the database administrator that the Oracle Reports Builder tables were not successfully installed in the database.

REP-00829
Oracle Reports Builder database tables are from an older version of Oracle Reports Builder ({0}): cancelling report.

Category:
Other

Cause:
Oracle Reports Builder tables in the database appear to have been installed from a previous version of the product. The report cannot run against an older version of the database tables.

Action:
Inform the database administrator that the Oracle Reports Builder tables for this version were not successfully installed in the database.

REP-00830
Oracle Reports Builder database tables appear to be corrupted or incorrectly installed: cancelling report.

Category:
Other

Cause:
The report cannot be run because the Oracle Reports Builder tables are in an unstable state.

Action:
Inform the database administrator that the Oracle Reports Builder tables are either corrupted or incorrectly installed in the database.

REP-00831
The query could not be built.

Category:
Other

Cause:
Oracle Reports Builder attempted to build a query at startup but it failed. One cause is that the database account against which the query was being built was not correct. Otherwise it is an abnormal condition.

Action:
If Oracle Reports Builder was launched from another product, check that the database connection string in the other product is correct.

REP-00900
The report cannot close while PL/SQL is still executing.

Category:
Other

Cause:
An attempt was made to close a report while associated PL/SQL was still executing.

Action:
Finish executing the PL/SQL or abort it, then close the report.

REP-00901
Tables and Columns function is not supported for this database server.

Category:
Other

Cause:
The connected database server does not have an accessible Data Dictionary to list tables and columns.

Action:
No action is needed. Tables and Columns functionality is not available for these databases.

REP-00910
The Cue Cards cannot be found. Reinstall the Cue Cards and try again.

Category:
Other

Cause:
An attempt was made to run the Cue Cards, where have not been properly installed.

Action:
Reinstall the Cue Cards.

REP-00911
The Oracle Reports page on OTN cannot be displayed. Reset the browser settings correctly.

Category:
Browser

Cause:
In the Welcome to Oracle Reports Builder dialog box, Getting Started was selected, which displays the Oracle Reports page on the Oracle Technology Network (OTN), but the browser settings are not set correctly.

Action:
1. Edit the Windows registry using a registry editor (for example, open a command prompt window and type regedit.exe). 2. Select File, then Export to back up the current registry settings. 3. Navigate to the following key: HKEY_CURRENT_USER\Software\Oracle\Toolkit\Tkbrowser. 4. Set the BrowserName and the BrowserPath values to the browser name and location. For example: BrowserName: Internet Explorer BrowserPath: C:\Program Files\Internet Explorer\iexplore.exe 5. Close the registry editor. 6. Shut down and restart Oracle Reports Builder. 7. In the Welcome to Oracle Reports Builder dialog box, select Getting Started and click OK. 8. In the Information Navigator Preferences dialog box that displays, specify the following values: - From the Browser list, select the desired browser (for example, Microsoft Internet Explorer). - In the Command to launch browser field, specify the correct path to the browser; click Browse to navigate to the correct path location. For example: C:\Program Files\Internet Explorer\iexplore.exe 9. Click OK to save the settings and display the Oracle Reports page on the Oracle Technology Network (OTN) using the specified browser.

REP-00999
Unimplemented Error:

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01010
This name does not conform to SQL naming standards.

Category:
Other

Cause:
The name entered violates one or more SQL naming conventions.

Action:
Name the object according to the appropriate naming conventions.

REP-01011
Object {0} must be named.

Category:
Other

Cause:
The Name field was left blank for the object and a name is required.

Action:
Name the object according to the appropriate naming conventions.

REP-01012
There is another {0} object with this name.

Category:
Other

Cause:
The name entered duplicates the name of another object of the same type.

Action:
Change the name of at least one of the objects.

REP-01013
This name may not be the same as a reserved word.

Category:
Other

Cause:
The name entered duplicates a reserved word.

Action:
Change the name of the parameter such that it conforms to parameter naming conventions.

REP-01014
The name length cannot exceed 30 bytes.

Category:
Other

Cause:
The name entered was greater than 30 bytes, which is the limit for SQL names.

Action:
Reduce the size of the name to 30 bytes or less.

REP-01048
Owner and Access list are not overwritten.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01049
A report saved with a newer version of Oracle Reports Builder cannot be opened.

Category:
Other

Cause:
An attempt was made to open a report with an older version of Oracle Reports Builder than the one with which the report was saved.

Action:
Use the same or a more recent version of Oracle Reports Builder to open the report.

REP-01050
Document names in the database cannot be accessed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01051
The document cannot be saved to file {0}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01052
The document cannot be saved to the database.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01053
A new document ID cannot be obtained from the database.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01054
Table {0} cannot be deleted from.

Category:
Other

Cause:
An attempt was made to delete from a table and the operation failed, possibly due to lack of necessary privileges.

Action:
Contact the system administrator to assign the necessary privileges to delete from the table.

REP-01055
Table {0} cannot be locked.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01056
Object stored in the database cannot be renamed.

Category:
Other

Cause:
An attempt was made to rename a database object and the operation failed, possibly due to lack of necessary privileges.

Action:
Make a copy of the object, or contact the system administrator to assign the necessary privileges to change the name.

REP-01057
File {0} is not a valid Oracle Reports Builder file.

Category:
Other

Cause:
An attempt was made to access a file that is not in the proper format for Oracle Reports Builder.

Action:
Verify that the correct file is being accessed.

REP-01058
The document cannot be read from the database.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01059
unable to read document from file {0}

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01060
Oracle Reports Builder database tables have not been installed.

Category:
Other

Cause:
Oracle Reports Builder failed to access the SRW2_MODULE view in the current database.

Action:
Verify Oracle Reports Builder was properly installed on the database. For help, contact the system administrator.

REP-01061
External file {0} cannot be read.

Category:
Other

Cause:
Read From File was activated and a file name specified as the value of a column, but Oracle Reports Builder could not successfully open or read the specified file.

Action:
Check the spelling of the specified file in the Column Property Inspector, and verif that the specified file exists. If the file does exist, check the permissions on the file for read access.

REP-01062
External query {0} cannot be found.

Category:
Other

Cause:
The possible causes of this error include the following: Case 1: REPORTS_PATH is not set. Case 2: There is no database connection. Case 3: The specified external query does not exist.

Action:
Take the following actions to correct this error: If Case 1: Set REPORTS_PATH to a valid value. If Case 2: Connect to a database. If Case 3: Specify the correct name of the external query.

REP-01063
The PL/SQL {0} has exceeded the platform specific size limit.

Category:
Other

Cause:
The PL/SQL could not be loaded because it is too large for the operating system. It may have been created on a different platform with a higher limit.

Action:
Reduce the size of the PL/SQL so it can be loaded on the platform.

REP-01064
Document {0} cannot be read.

Category:
Other

Cause:
An attempt was made to open a document whose definition, stored in either the database or the filesystem, has been lost or corrupted.

Action:
This document cannot be used.

REP-01065
External query {0} cannot be read.

Category:
Other

Cause:
An attempt was made to read an external query whose definition, stored in either the database or the filesystem, has been lost or corrupted.

Action:
This external query cannot be used.

REP-01066
Comment is corrupted and will be lost.

Category:
Other

Cause:
A storage error caused a comment to be corrupted. It will be discarded.

Action:
No action is necessary. If desired, re-create the comment in the designer.

REP-01067
Some information is missing in the report.

Category:
Other

Cause:
The report cannot be opened because the report definition is incomplete. It may have been corrupted.

Action:
If the report is stored in the database, use SQL*Plus to determine whether the Oracle Reports Builder tables have been corrupted. If the report is an .rdf file, use a file system utility to check if the file is corrupted. Take appropriate actions to recover the data.

REP-01070
An error occurred while opening or saving a document.

Category:
Other

Cause:
An error occurred while opening or saving a document.

Action:
Verify the access privileges for the document.

REP-01071
The end of an object or record scan was reached.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01072
The object cannot be found in the object store.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01073
The object was found in the object store when not expected.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01074
The object is too big.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01075
The object is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01076
The specified object store is invalid.

Category:
Other

Cause:
An attempt was made to use an invalid file or database object.

Action:
Verify that the object specified is a valid Oracle document, stored in a file or in the database.

REP-01077
The type specified for the object is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01078
A non-specific file error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01079
The function is unsupported.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01080
A unique key violation occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01081
A page split occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01082
A close error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01083
A file version error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01084
A file header is bad or missing.

Category:
Other

Cause:
An operation required Oracle Reports Builder to open a file. The file either did not have a header or it did not have the expected header. The header may have been changed in an editor or the file may not be compatible with this release of Oracle Reports Builder.

Action:
Attempt to fix the header in an editor, although it is not recommended that Oracle Reports Builder files be edited in this way. For assistance, contact Oracle Support Services.

REP-01085
A file create error occurred.

Category:
Other

Cause:
An operation that required Oracle Reports Builder to create a file failed, most likely due to insufficient privileges to create the file.

Action:
Obtain the necessary privileges for the file.

REP-01086
A file open read-only error occurred.

Category:
Other

Cause:
An operation that required Oracle Reports Builder to open a file failed, most likely due to insufficient privileges to open the file.

Action:
Obtain the necessary privileges for the file.

REP-01087
A file open read-write error occurred.

Category:
Other

Cause:
An operation that required Oracle Reports Builder to open a file failed, most likely due to insufficient privileges to open the file.

Action:
Obtain the necessary privileges for the file.

REP-01088
A file write error occurred.

Category:
Other

Cause:
An operation that required Oracle Reports Builder to write to a file failed, most likely due to insufficient file privileges to write to the file.

Action:
Obtain the necessary privileges for the file.

REP-01089
A file read error occurred.

Category:
Other

Cause:
An operation that required Oracle Reports Builder to read a file failed, most likely due to insufficient file privileges to read the file.

Action:
Obtain the necessary privileges for the file.

REP-01090
A file close error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01091
The disk or file system is full.

Category:
Other

Cause:
An attempt was made to save an object, but there was not enough space in which to save it.

Action:
Either delete some unnecessary files or expand the storage space.

REP-01092
A file unique key violation occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01093
Allocate failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01094
Reallocate failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01095
Free failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01096
The document {0} is currently locked.

Category:
Other

Cause:
An attempt was made to open a document that is already opened (locked) by another user.

Action:
Wait until the other user closes the document before accessing it.

REP-01097
PRODUCT_USER_PROFILE or SYSTEM.PRODUCT_PROFILE does not exist.

Category:
Other

Cause:
The possible causes of this error include the following: Case 1: The table does not exist. Case 2: The necessary privileges to access the table are not granted.

Action:
Take the following actions to correct this error: If Case 1: If the table is not already created, create it. If Case 2: Get access to the table by creating a public synonym for the table in the PRODUCT_USER_PROFILE table, or by making the table public via the PRODUCT_USER_PROFILE table.

REP-01098
An error occurred reading PRODUCT_USER_PROFILE or SYSTEM.PRODUCT_PROFILE data.

Category:
Other

Cause:
The table is not created correctly.

Action:
Ensure that the table was created with the appropriate columns. If it was not, then modify it as necessary.

REP-01099
Files not created with Oracle Reports Builder cannot be opened.

Category:
Other

Cause:
An attempt was made to open a file that is not an Oracle Reports Builder report.

Action:
Verify that the file is an Oracle Reports Builder report.

REP-01100
The data model is invalid for this type of report.

Category:
Data

Cause:
An attempt was made to create a default layout with a layout style that does not match the data model.

Action:
Either change the data model to match the selected layout style or select a different layout style to match the data model. For more information, see the Oracle Reports online help.

REP-01101
Group {0} has an invalid repeat direction.

Category:
Other

Cause:
An attempt was made to create a default layout, but the selected layout style requires a different repeat direction for one of the groups. Some layout styles place restrictions on the repeat directions that can be selected for groups.

Action:
Either change the repeat direction to meet the layout style requirements or select a different layout style.

REP-01102
The default layout cannot fit onto page of size {0}.

Category:
Other

Cause:
Oracle Reports Builder tried to create the default layout selected but could not fit the entire layout on the page because the page is not wide enough.

Action:
If possible, increase the Page Width on the Report Property Inspector or rearrange objects such that the layout will fit on the page. Otherwise, make the report multiple pages wide.

REP-01103
No column is selected in group {0}.

Category:
Other

Cause:
While trying to create a default layout, a column was not selected for a selected group. Consequently, Oracle Reports Builder cannot build a default layout because one or more of the dimensions of the layout have no value.

Action:
In the Report Wizard, select at least one column from each selected group.

REP-01104
Page level summaries are not supported in the default layout.

Category:
Other

Cause:
A default layout was generated that does not fit within the given amount of space. The possible causes of this error include the following: Case 1: The layout generated is too large given the dimensions specified in the Report Properties dialog box. Case 2: The layout is too big given the size of the marked area in the Paper Layout editor.

Action:
Take the following actions to correct this error: If Case 1: Increase the report dimensions such that the layout can fit, or alter the layout so that it will fit within the current dimensions. If Case 2: Increase the size of the marked area.

REP-01106
no field is generated for column {0}.

Category:
Other

Cause:
When the default layout was created, a field was not generated for the column in the message. The most likely cause is that a summary was not placed in the data model correctly. For example, the source of a summary column may have been specified to be a column in a group above the summary's group, which is not allowed.

Action:
Debug the data model and redefault the layout.

REP-01107
The across or down group in cross product group {0} is missing.

Category:
Other

Cause:
An attempt was made to create a default layout by selecting a Style of Matrix in the Report Wizard, but all of the dimension groups of the cross product group were assigned repeat directions of Down or Across. Each repeat direction should be assigned to the dimension groups in the cross product.

Action:
Redisplay the Report Wizard and reassign the repeat directions of the dimension groups, making sure that each direction is assigned among the groups.

REP-01108
The default layout cannot fit even in region extending to page boundaries.

Category:
Other

Cause:
An attempt was made to create a default layout that would be too large to fit within the defined height and width of a report page.

Action:
Go back to the Report Wizard and reduce the values of default settings (for example, shorten some field widths). Alternatively, increase the size of a report page using the Report Property Inspector. Then re-create the default layout.

REP-01109
Multiple group selection is incompatible with single group layout style.

Category:
Other

Cause:
More than one group was selected to add to the layout but the style selected only supports one group.

Action:
Change the group selection so that only a single group is selected. Alternatively change the layout style to one that supports multiple groups.

REP-01110
The matrix across group in cross product group {0} is missing.

Category:
Other

Cause:
An attempt was made to create a default layout by selecting a Style of Matrix or Matrix with Group in the Report Wizard, but all of the dimension groups of the cross product group were assigned repeat directions of Down.

Action:
Change the repeat direction of one of the cross product dimension groups so that there is at least one Across group and one Down group.

REP-01111
The matrix down group in cross product group {0} is missing.

Category:
Other

Cause:
An attempt was made to create a default layout by selecting a Style of Matrix or Matrix with Group in the Report Wizard, but all of the dimension groups of the cross product group were assigned repeat directions of Across.

Action:
Change the repeat direction of one of the cross product dimension groups so that there is at least one Down group and one Across group.

REP-01112
The matrix cross product group in the matrix report is missing.

Category:
Other

Cause:
An attempt was made to create a default layout by selecting a Style of Matrix or Matrix with Group in the Report Wizard, but a cross product group was not selected to be used as the matrix group.

Action:
Change the repeat direction of one of the cross product group to Matrix.

REP-01113
No groups or reports level columns have been selected.

Category:
Other

Cause:
While trying to create a default layout, no groups or report level columns were selected. Consequently, Oracle Reports Builder cannot build a default layout because one or more of the dimensions of the layout have no value.

Action:
In the Report Wizard, select at least one report level column or a group to be defaulted.

REP-01114
A single group selection is incompatible with a multiple group layout style.

Category:
Other

Cause:
A single group was selected to be defaulted but a defaulting style designed for a multiple groups was also selected.

Action:
Change the group selection so that more than one group is selected. Alternatively, change the layout style to one that supports single groups.

REP-01115
The full template layout cannot be shown because it does not fit onto the page.

Category:
Other

Cause:
The template layout could not be shown properly because it is too large to fit within the defined height and width of the report page. This does not mean that the template is invalid in any way.

Action:
To show the template layout, temporarily enlarge the width and height of the report page. To do this, select the template in the Navigator and open the Property Inspector. Increase the Width and Height properties under the Report heading. Do not forget to reset the Width and Height properties before saving the template.

REP-01118
A cross product group in the Matrix query is missing.

Category:
Other

Cause:
An attempt was made to create a query by selecting the Matrix query option in the Data Wizard, However, the cross product group does not exist in the query to be used as the matrix group.

Action:
Restart the Data Wizard.

REP-01200
The flow compilation failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01201
Query text is missing from query {0}.

Category:
Other

Cause:
A query was named, but either no SELECT statement was entered for it or something that did not begin with the keyword SELECT was entered. The SQL Query Statement dialog box only accepts SQL SELECT statements.

Action:
Enter a SQL SELECT statement that begins with the word SELECT (upper or lower case may be used).

REP-01202
An Oracle logon was not specified.

Category:
Other

Cause:
An attempt was made to run a report without an Oracle logon specified.

Action:
Enter a logon string in the Connect dialog box and accept the dialog box before rerunning the report.

REP-01203
Field {0} references an invalid column.

Category:
Other

Cause:
The column specified as the field's Source either is invalid or does not exist.

Action:
Select a column from the list of values.

REP-01204
Repeating frame {0} references an invalid group.

Category:
Other

Cause:
The group name specified in the Group field of the Repeating Frame Property Inspector either is invalid or does not exist.

Action:
Select a group from the list of values.

REP-01205
There is a loop in the positional dependency tree.

Category:
Other

Cause:
Explicit anchors were created such that an object is indirectly anchored to itself. For example, if object A was anchored to object B, object B to object C, and object C to object A, this error displays.

Action:
Remove at least one of the anchors that caused the loop.

REP-01206
An object is anchored to more than one other object.

Category:
Other

Cause:
In the layout, an object was anchored to more than one other object.

Action:
Eliminate the anchors to other objects such that the object is anchored to only one other object.

REP-01207
The PL/SQL procedure for group filter {0} is missing.

Category:
Other

Cause:
The Filter Type on the Group Property Inspector specified a vlue of PL/SQL, but a valid filter was not specified.

Action:
Enter a valid PL/SQL function or change the filter type.

REP-01208
A repeating frame of matrix {0} cannot be anchored.

Category:
Other

Cause:
An attempt was made to run a report with an anchor from an intersecting repeating frame of a matrix object to another object.

Action:
Delete the anchor.

REP-01209
Matrix {0} cannot be anchored.

Category:
Other

Cause:
An attempt was made to run a report with an anchor from a matrix object to another object, which is not allowed.

Action:
Delete the anchor.

REP-01211
Object {0} is larger than its enclosing object {1}.

Category:
Other

Cause:
An object is larger than its enclosing object. The most likely cause is that an attempt was made to enclose a large object within a small, fixed frame.

Action:
Identify the object and the enclosing object and adjust their relative sizes and positions until the proper enclosure is achieved.

REP-01212
Object {0} is not fully enclosed by its enclosing object {1}.

Category:
Other

Cause:
The possible causes of this error include the following: Case 1: An object is not fully enclosed by the page. That is, the object extends beyond the page boundary. Case 2: A repeating frame that forms a matrix is one or more layers above a repeating frame that it contains. In a matrix layout, repeating frames must be below repeating frames that they contain.

Action:
Take the following actions to correct this error: If Case 1: Move or resize the object so that it does not extend outside the page boundary. Alternatively, increase the page size in the Report

Property Inspector. If Case 2: Use Arrange>Send to Back, Arrange>Bring to Front, Arrange>Move Backward, and Arrange>Move Forward to arrange repeating frames such that, in terms of layers, the following is true: repeating frames are below repeating frames that they contain and down repeating frames are below across repeating frames.

REP-01213
Field {0} references column {1} at a frequency below its group.

Category:
Other

Cause:
The source column for the field is in a group below that of the repeating frame that encloses it.

Action:
Move the field into a repeating frame whose source group is at or above the group that contains the field's source column. Otherwise, move the field's source column into the enclosing repeating frame's group, if possible.

REP-01214
Repeating frame {0} is enclosed by a child repeating frame.

Category:
Other

Cause:
The enclosed repeating frame's source group is above the enclosing repeating frame's source group.

Action:
In the editor, make the enclosed repeating frame the enclosing repeating frame. Alternatively, if possible, change the group hierarchy such that the enclosed object's group is below the enclosing object's group.

REP-01216
Object {0} has an illegal print condition.

Category:
Other

Cause:
The Print Condition for the specified object was invalid. For example, an attempt may have been made to set the Print Condition of a margin object.

Action:
Change the Print Condition of the object to another, valid setting.

REP-01218
Object {0} cannot page break before AND keep with parent.

Category:
Other

Cause:
Page Break Before was set for an object as well as Keep with Anchoring Object. The anchoring object, however, precedes the object and therefore the two settings are in conflict.

Action:
Uncheck Page Break Before or Keep with Anchoring Object.

REP-01219
Object {0} has no size; length or width is zero.

Category:
Other

Cause:
A layout object was created of zero width or height.

Action:
Enlarge the opject so that it has a non-zero height and width.

REP-01220
Object {0} has Minimum Widow Records greater than Maximum Records per Page.

Category:
Other

Cause:
Maximum Records per Page was set to a smaller value than Minimum Widow Records. This causes a conflict between the two settings and, in effect, indicates that no instances should be printed.

Action:
Decrease Minimum Widow Records or increase Maximum Records per Page.

REP-01222
The body size is invalid.

Category:
Other

Cause:
A body page width or height was specified that is negative or out of range. This is most likely due to setting the page size to an invalid value using the PAGESIZE executable argument.

Action:
Enter a valid value using the PAGESIZE executable argument, or adjust the body panel size by resizing the margins in the Paper Layout editor.

REP-01223
The page size is invalid.

Category:
Other

Cause:
A physical page width or height was specified that is negative or out of range. This is most likely due to setting the page size to an invalid value using the PAGESIZE executable argument.

Action:
Enter a valid value using the PAGESIZE executable argument, or change the physical page size setting in the Report Property Inspector.

REP-01225
The logical page size is invalid.

Category:
Other

Cause:
A logical page height was specified that is negative.

Action:
Redefine the logical panel height to ensure that it is not defined using a negative number.

REP-01226
The body location is beyond the print area.

Category:
Other

Cause:
The body panel is not enclosed within the physical page.

Action:
Adjust the body panel size by resizing the margins in the Paper Layout editor.

REP-01229
The spacing between records for repeating frame {0} is negative.

Category:
Other

Cause:
The value for Vertical Spacing and/or Horizontal Spacing specified for a repeating frame is negative.

Action:
Respecify the appropriate Spacing setting for the repeating frame.

REP-01230
Field {0} has an invalid page reset group.

Category:
Other

Cause:
In the Reset At field of the Page Numbering dialog box, a repeating frame was specified that does not enclose the layout field that should display the page number. An invalid repeating frame may have been specified, or the repeating frame was deleted after specifying it.

Action:
Specify &Report or the name of a valid repeating frame as the Reset At value for the page number field.

REP-01231
Object {0} has an invalid text wrap style.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01232
Matrix {0} has an invalid source frame.

Category:
Other

Cause:
An invalid object was specified as the source frame of the matrix object, or the repeating frames specified have invalid Print Directions.

Action:
Change the Print Direction of horizontal source repeating frame to Down, and the Print Direction of the vertical source repeating frame to Across.

REP-01233
The frames of matrix {0} do not fully intersect.

Category:
Other

Cause:
The repeating frames that form the matrix do not completely intersect. For example, if there are two down repeating frames, two across repeating frames, and one of the across repeating frames only intersects completely with one of the down repeating frames, this error displays.

Action:
Redefault the matrix layout, if possible, or move the repeating frames that make up the matrix such that they fully intersect one another.

REP-01234
The position of matrix {0} is not at the intersection of its frames.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01235
An error occurred generating index for Cross Product.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01236
Query {0} is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01237
The data link is invalid.

Category:
Data

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01238
Group {0} is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01239
Column {0} is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01240
The anchor is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01241
A circular column dependency originating with column {0} exists.

Category:
Other

Cause:
A column was created that directly or indirectly references itself. For example, Column A might reference Column B which in turn references Column A.

Action:
Update or delete columns to eliminate the circular dependency.

REP-01242
Matrices must have all down frames below all across frames.

Category:
Other

Cause:
In a matrix layout, down repeating frames must be below across repeating frames.

Action:
Using Arrange>Send to Back, Arrange>Bring to Front, Arrange>Move Backward, and Arrange>Move Forward, arrange repeating frames such that, in terms of layers, the following is true: repeating frames are below repeating frames that they contain, and down repeating frames are below across repeating frames.

REP-01243
An unimplemented type of summary is specified in column {0}.

Category:
Other

Cause:
A summary function was specified that is not available.

Action:
Specify a valid summary function.

REP-01245
The wrong number of source columns are defined for summary function of column {0}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01246
The graph document is not found.

Category:
Other

Cause:
Oracle Reports Builder cannot find the associated graph document for the graph.

Action:
Correct the file name and path of the graph document.

REP-01247
The report contains uncompiled PL/SQL.

Category:
Other

Cause:
An attempt was made to run the report before all referenced PL/SQL constructs was compiled.

Action:
Compile the PL/SQL, then run the report.

REP-01248
All source columns of placeholder {0} must be in the same group.

Category:
Other

Cause:
An attempt was made to set the value of a placeholder column from columns belonging to different groups.

Action:
Change the placeholder column's group to match the group of the columns changing the placeholder column's value.

REP-01249
Column {0} has no PL/SQL formula.

Category:
Other

Cause:
A column of Type Formula was created with nothing in the Formula field.

Action:
Create a formula for the column or change the column's Type.

REP-01250
A circular query dependency exists.

Category:
Other

Cause:
The report contains at least two queries, with each requiring the other to be executed first.

Action:
Edit one or more of the queries to remove the circular dependency.

REP-01251
A circular query dependency originating with query {0} exists.

Category:
Other

Cause:
The report contains at least two queries, with each requiring the other to be executed first. The query listed in the message is one of the conflicting queries.

Action:
Edit the query listed or another conflicting query to remove the circular dependency.

REP-01252
The matrix should be surrounded by a repeating frame on group {0}.

Category:
Other

Cause:
The data model for the report contains a matrix with a parent group, but in the layout the repeating frame for the parent group either does not exist or does not surround the matrix.

Action:
Modify the layout of the report so that the parent group has a repeating frame that surrounds the matrix.

REP-01253
Matrix objects are on different regions of the layout.

Category:
Other

Cause:
The repeating frames of a matrix are on different regions of the layout (body, margin, header, or trailer).

Action:
Move all repeating frames of the matrix to the same report region.

REP-01254
Anchored objects are on different regions of the layout.

Category:
Other

Cause:
The anchoring and anchored objects of an anchor are on different regions of the layout (body, margin, header, or trailer).

Action:
Move the above-mentioned objects to the same report region.

REP-01255
An object cannot anchor to a hidden object.

Category:
Other

Cause:
The anchored object of an anchor is a hidden object.

Action:
Either make the anchored object not hidden, or delete the anchor.

REP-01256
File link boilerplate text is missing its source file.

Category:
Other

Cause:
A file name was not specified in the Source Filename property for the file link boilerplate object.

Action:
Specify a directory path and file name in the Source Filename property in the file link boilerplate object's Property Inspector.

REP-01257
Oracle Reports Builder cannot fetch data for child query from caller.

Category:
Data

Cause:
Oracle Reports Builder was invoked from another product, and Oracle Reports Builder has been instructed to fetch data for a child query from the caller. Data passed to Oracle Reports Builder can only be for a master query.

Action:
Modify the caller's instructions so that Oracle Reports Builder does not request data for a child query.

REP-01258
Group {0} has no columns.

Category:
Other

Cause:
A group was created that has no columns.

Action:
Delete the group or assign one or more columns to the group.

REP-01259
Group {0} has no break columns.

Category:
Other

Cause:
A parent group was created that has no break columns.

Action:
Mark the Break Order check boxex of the break columns of the group.

REP-01260
Groups {0} and {1} are from the same query and cannot be linked.

Category:
Other

Cause:
Two groups from the same query were linked with a data link, which is not allowed.

Action:
Remove the data link or relink to another group.

REP-01261
Group {0} can have only one parent.

Category:
Other

Cause:
One group has two queries as its parent (it can only have one).

Action:
Remove data links from the same group to different queries.

REP-01262
A circular data link dependency starting from group {0} exists.

Category:
Data

Cause:
A cycle with data links was created (that is, a parent was specified as the child of itself, either directly or indirectly).

Action:
Remove at least one of the links in the cycle.

REP-01263
Cross product group {0} has no or only one dimension group.

Category:
Other

Cause:
A cross product group was defined that has no or only one group inside. Cross product groups must have at least two dimension groups. Multiquery cross product groups must have at least two queries within the cross product group.

Action:
Remove the cross product group or add dimension groups, or dimension queries (if multiquery).

REP-01264
A data link of group {0} crosses cross a product boundary.

Category:
Data

Cause:
In the multiple-query matrix report, a query has some of its groups are inside the cross product and some outside.

Action:
Move all groups of the query to either outside or inside of the cross product group.

REP-01265
A cross product group {0} has no child groups.

Category:
Other

Cause:
A cross product group has no child group, which is required. The child group acts as the cell of the matrix.

Action:
Create a child group for the cross product group.

REP-01266
Page Level column {0} is not allowed in a cross product.

Category:
Other

Cause:
A column was creted in a cross product group that is or relies on a column that is a page-level summary (that is, a summary with Reset At of Page).

Action:
Remove the column from the cross product group, or change the Reset At value of the column or the page-level summary upon which it relies.

REP-01267
Graph {0} references an invalid column as a bind parameter.

Category:
Other

Cause:
The graph references a column that does not exist. An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01268
Graph {0} references a bind column {1} at the wrong frequency.

Category:
Other

Cause:
The column specified for the graph is in a group below that of the repeating frame that encloses the graph.

Action:
Move the graph into a repeating frame whose source group is at or above the group that contains the specified column. Otherwise, move the specified column into the enclosing repeating frame's group, if possible.

REP-01269
Graph {0} references an invalid report group.

Category:
Other

Cause:
The report group specified for the graph does not exist. An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01270
Graph {0} references a report group at the wrong frequency.

Category:
Other

Cause:
The report group specified for the graph is above the source group of the enclosing repeating frame.

Action:
Move the graph into a repeating frame with a source group that is at or above its report group.

REP-01271
Graph column name {1} has been specified multiple times in the graph document {0}.

Category:
Other

Cause:
The specified graph column or parameter has been referenced more than once in the graph document.

Action:
Check the columns and parameters specified for the graph and delete any duplicates.

REP-01272
Column {0} may not be used as a break column.

Category:
Other

Cause:
A Break Order was specified on a summary, function, or placeholder. These types of columns cannot be used as break columns.

Action:
Review the rules for which columns can be break columns. For more information, see the online help topic 'Break Order property'.

REP-01273
Source groups of matrix {0} are not from the same cross product.

Category:
Other

Cause:
The source groups of the repeating frames that form the dimensions of the matrix are not contained by the same cross product group. The dimensions of a matrix must be contained within the same cross product group.

Action:
Change the source groups of the repeating frames or select different repeating frames to form the dimensions of the matrix.

REP-01274
Invalid repeat direction combination in matrix {0}.

Category:
Other

Cause:
Matrix dimension repeating frames whose source groups are in the same "family" hierarchy (that is, are descendants or ancestors of each other) within a cross product group must have the same Print Direction. Parent-child relationships within a cross product group are used to create nesting in the matrix. As a result, the repeating frames associated with such groups must print in the same direction on the page.

Action:
Change the Print Direction of the repeating frames as necessary, select different source groups for the repeating frames, or select different repeating frames to form the dimensions of the matrix.

REP-01275
Page level column {1} may not be referenced from format trigger {0}.

Category:
Other

Cause:
PL/SQL was entered in a Format Trigger that references columns with a Reset At or Compute At of Page.

Action:
Remove the reference to the page-level column or change the column's Reset At or Compute At to something other than Page.

REP-01276
Placeholder {0} references one or more non-formula columns.

Category:
Other

Cause:
A placeholder column contains SRW.REFERENCE, but the column referenced is not a formula column. For placeholder columns, SRW.REFERENCE must refer to a formula column.

Action:
Change the column referenced via SRW.REFERENCE.

REP-01277
The SELECT element is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01278
The PL/SQL procedure in {0} is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01279
Frame or repeating frame {0} is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01280
Field {0} is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01281
Boilerplate {0} is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01282
Matrix {0} is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01283
Graph document {0} is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01284
Query {0} has no groups.

Category:
Other

Cause:
The data model contains a query that has no groups. Each query in the data model needs at least one group associated with it.

Action:
Create a new group for the query.

REP-01285
Query {0} has no SELECT elements.

Category:
Other

Cause:
The data model contains a query that does not select anything. Each query in the data model must select at least one element.

Action:
Enter a SELECT statement in the query, selecting at least one element.

REP-01286
Group {0} is a cross product as well as a dimension.

Category:
Other

Cause:
A group was specified to act as both a cross product group and as a dimension group for another cross product group, which is not allowed.

Action:
Make the group either a cross product group or a dimension group, but not both.

REP-01287
Cross product group {0} may not have a group filter.

Category:
Other

Cause:
A group filter was specified on a cross product group, which is not allowed.

Action:
Remove the group filter from the cross product group. Create the group filter for another group, if necessary.

REP-01288
The numeric argument for group filter of group {0} is missing.

Category:
Other

Cause:
First or Last was specified for a group's filter, but a number dictating how many records the group should filter was not specified.

Action:
Specify a number for the group filter.

REP-01289
An unimplemented type of group filter is specified in group {0}.

Category:
Other

Cause:
A group filter was specified that is not available or is invalid.

Action:
Specify a valid group filter for the group.

REP-01290
The Source data type is incompatible with the summary function in column {0}.

Category:
Data

Cause:
The summary column was assigned a Source whose data type is incompatible with the specified Function. For example, a temp may have been made to sum a character column.

Action:
Verify that the data type of the source column is compatible with the Function specified in the Summary Column Property Inspector.

REP-01291
Column {0} has an invalid reset group.

Category:
Other

Cause:
An invalid Reset At value was specified for a summary column. Reset At can be set to the same group as the summary column, any group above the summary column's, Page, or Report.

Action:
Specify a valid Reset At value for the summary column in its Property Inspector.

REP-01292
Column {0} has an invalid compute group.

Category:
Other

Cause:
An invalid Compute At value was specified for a summary column. Compute At can be set to the same group as the summary column, any group above the summary column's, Page, or Report.

Action:
Specify a valid Compute At value for the summary column in its Property Inspector.

REP-01293
Column {0} has an invalid product order.

Category:
Other

Cause:
A column in a cross product group was assigned an invalid value for Product Order, or no value at all.

Action:
Specify a valid value for Product Order (consisting of only dimension groups within the cross product) in the column's Property Inspector.

REP-01294
The width of column {0} is too large.

Category:
Other

Cause:
The column's width exceeds the maximum allowed for the operating system.

Action:
Reduce the width of the column in the Column Property Inspector.

REP-01295
The data format of column {0} is unsupported.

Category:
Data

Cause:
Read from File was selected for a column, but an invalid or unavailable data format was specified in the Format field in the Column Property Inspector.

Action:
Specify a valid data format in the Format field. The list of values displays all valid data formats. Note that for LONG, RAW, and LONG RAW database columns, only Text and Oracle Format (Image) are valid values for Format.

REP-01296
The data link child cannot be in the cross product group {0}.

Category:
Data

Cause:
An attempt was made to link a column to a column in a cross product group, or to the cross product group itself.

Action:
Create data links between columns and groups other than cross product groups and their associated columns.

REP-01297
The data link child column {0} must be a database column.

Category:
Data

Cause:
An attempt was made to link a column to another column that is not a database column (for example, a summary, formula, or placeholder column).

Action:
Create data links using only database columns and groups.

REP-01298
Columns {0} and {1} have incompatible types to be linked.

Category:
Other

Cause:
The parent and child columns in the data link have incompatible datatypes that cannot be linked. For example, an attempt was made to link a Number column to a Character column.

Action:
Verify that the parent and child columns specified in data links have compatible datatypes.

REP-01299
Groups {0} and {1} in different cross products cannot be linked.

Category:
Other

Cause:
An attempt was made to create a data link between dimension groups of two different cross product groups, or between columns of the dimension groups.

Action:
Delete data links between two different cross product groups or their columns.

REP-01300
Text boilerplate {0} has no contents.

Category:
Other

Cause:
A text boilerplate object was created that contains no text.

Action:
Enter some text in the boilerplate object, or delete it.

REP-01301
The data link creates a sibling of group {0} within a cross product.

Category:
Data

Cause:
A data link was defined that created a sibling of a dimension group within a cross product group. No siblings of dimension groups are allowed within the cross product.

Action:
Delete the sibling of the dimension group.

REP-01302
The cross product has two or more child groups.

Category:
Other

Cause:
A cross product group has more than one child group. Only one child is allowed per cross product group.

Action:
Remove all but one of the child groups to the cross product group.

REP-01303
The query must be completely in or out of cross product group {0}.

Category:
Other

Cause:
A query was created whose groups are not all inside the cross product, above the cross product, or below the cross product, respectively.

Action:
Verify that each query's groups are all inside of a cross product, above a cross product, or below a cross product.

REP-01304
Cross product group {0} contains another cross product as child.

Category:
Other

Cause:
A cross product group was created that is a child of another cross product group, which is not allowed.

Action:
Ensure that the child group of the cross product group is not a cross product group.

REP-01305
Frame {0} intersects but does not enclose object {1}.

Category:
Other

Cause:
The report layout contains a frame that does not completely enclose the named object. Thus, the object is not considered to be inside the frame.

Action:
To enclose the object with the frame, resize or move the frame.

REP-01306
Summary column {0} has an invalid source.

Category:
Other

Cause:
An invalid source was specified for the summary column. A summary column's source must be from the same group as the summary column, or from a group below the summary column.

Action:
Change the source of the summary column to be from the same group as the summary column or from a group below the summary column.

REP-01307
Summary column {0} has an invalid product order.

Category:
Other

Cause:
The possible causes of this error include: Case 1: A summary exists that is not a running summary (that is, its Reset At is not Report), but its Product Order is not a subset of the source column's product order. The source column of the summary must be at least as frequent as the summary, which means that the summary's Product Order should be some subset of the source column's Product Order. Case 2: A running summary (that is, its Reset At is Report) exists with a Product Order that is not a prefix of the source column's Product Order. For example, if the source column's Product Order were A,B,C, then the summary

column's Product Order would have to be either A (by itself) or A,B. The summary's Product Order could not be B,A.

Action:
Take the following actions to correct this error: If Case 1: Change the Product Order of the summary such that it is a subset of its source column's Product Order. If Case 2: Change the Product Order of the summary such that it is a prefix of the Source column's Product Order.

REP-01308
Placeholder column {0} is not supported in a cross product.

Category:
Other

Cause:
An attempt was made to create a placeholder column inside of a cross product group. Cross product groups cannot contain placeholder columns.

Action:
Delete the placeholder or move it outside the cross product group.

REP-01309
Report level summary {0} cannot be a percent of total.

Category:
Other

Cause:
A summary was created at the report-level (that is, a summary outside of all the groups in the data model) with a Function of % of Total. This Function makes no sense for a report-level summary because it will always be 100%.

Action:
Delete the summary or move it into a group where it will make sense.

REP-01310
Boilerplate {0} references &{1} which is not a field.

Category:
Other

Cause:
A boilerplate object has a reference to a field that does not exist. It could be that the field being referenced was deleted or renamed and so this reference in the boilerplate object is now invalid.

Action:
Depending on circumstances, remove the reference, replace it with a reference to another field, or create the field that it references.

REP-01311
Object {0} with page-dependent references have been changed to fixed sizing.

Category:
Other

Cause:
A field or boilerplate object has a reference to a page calculation or a total number of pages variable. (This is known as a forward reference.) Such layout objects must be fixed in size both horizontally and vertically.

Action:
The layout object's Horizontal and Vertical Elasticity have been set to Fixed by Oracle Reports Builder. Check the output to ensure that the values are not being truncated. If they are, enlarge the layout object so that it is large enough to contain the values.

REP-01312
Page-level column {1} may not be referenced from graph {0}.

Category:
Other

Cause:
A column passed to a graph is or depends upon a page-level summary (that is, a summary with a Reset At or Compute At of Page). A column being passed to a graph cannot be or depend upon a page-level summary.

Action:
Do not pass the column to the graph.

REP-01313
Page-level column {1} may not be referenced from group filter {0}.

Category:
Other

Cause:
A column that was referenced in a group filter is or depends upon a page-level summary (that is, a summary with a Reset At or Compute At of Page). A column referenced by a group filter cannot be or depend upon a page-level summary.

Action:
Do not reference the column in the group filter.

REP-01314
Format trigger {0} references column {1} at the wrong frequency.

Category:
Other

Cause:
A format trigger references a column that is located at the wrong frequency.

Action:
Remove the reference to the column from the format trigger.

REP-01315
Group filter {0} references column {1} at the wrong frequency.

Category:
Other

Cause:
A group filter attempted to reference a column that is inaccessible.

Action:
Remove the reference to the column from the group filter.

REP-01316
Object {0} references column {1} at the wrong frequency.

Category:
Other

Cause:
A procedure or function attempted to reference a column that is inaccessible.

Action:
Remove the reference to the column from the PL/SQL subprogram.

REP-01317
Boilerplate {0} references field with source {1} at the wrong frequency.

Category:
Other

Cause:
A boilerplate object referenced a field using &fieldname, but the two objects are not located at the same frequency. For example, the boilerplate object and the field it references are located within different repeating frames.

Action:
Place the boilerplate object and field at the same frequency, or remove the reference.

REP-01318
An error occurred while setting transaction to read-only.

Category:
Transactioning

Cause:
Having specified READONLY=YES, this error occurred at the start of report execution, while ending the current transaction (with a COMMIT) and starting the read-only transaction, or at the end of report execution, while ending the read-only transaction (with a COMMIT).

Action:
Verify the database connection, and verify that that no cursors or locks were left pending by the previous transaction.

REP-01319
Implicit anchoring algorithm cannot uniquely identify the anchoring object {0}. Arbitrarily choosing {1}.

Category:
Other

Cause:
The specified object (object1) is in the "push path" of two objects and it is equidistant from both objects. As a result, Oracle Reports Builder cannot use its normal criteria (shortest distance) to determine the implicit anchor. In the absence of its normal criteria, Oracle Reports Builder randomly creates an implicit anchor to the specified object (object2). Note that the implicit anchor may vary between runs of the report.

Action:
To avoid the random creation of an implicit anchor, explicitly anchor the specified object (object1) to another object.

REP-01320
Program unit {0} references a column with invalid ID {1}.

Category:
Other

Cause:
A report was run containing invalid PL/SQL (for example, PL/SQL that did not compile). The PL/SQL source included a column reference that cannot be resolved.

Action:
Check the column references in the PL/SQL source, recompile all of the PL/SQL source in the report, and rerun the report.

REP-01322
Page break after on object {0} has no effect.

Category:
Other

Cause:
A Page Break After was activated on an object that has no other objects anchored to it (implicitly or explicitly). In this case, Page Break After has no effect and is invalid. Notice that this is a warning, not an error message.

Action:
Deactivate Page Break After for the object.

REP-01323
Output columns in format trigger {0} are not allowed.

Category:
Other

Cause:
In the format trigger for the specified object, an attempt was made to set the value of an Oracle Reports Builder column parameter. For example, the value of a column called COUNT1 can be used in a condition (for example, IF :COUNT1=10), but its value cannot be directly set in an assignment statement (for example, COUNT1=10).

Action:
Remove the assignment statement from the format trigger.

REP-01324
Output columns in group filter {0} are not allowed.

Category:
Other

Cause:
In the filter for the specified group, an attempt was made to set the value of an Oracle Reports Builder column or parameter. For example, the value of a column called COUNT1 can be used in a condition (for example, IF :COUNT1=10), but its value cannot be directly set in an assignment statement (for example, COUNT1=10).

Action:
Remove the assignment statement from the group filter.

REP-01325
Output columns in a Between Page Trigger are not allowed.

Category:
Other

Cause:
In the Between Page trigger, an attempt was made to set the value of an Oracle Reports Builder column or parameter. For example, the value of a column called COUNT1 can be used in a condition (for example, IF :COUNT1=10), but its value cannot be directly set in an assignment statement (for example, COUNT1=10).

Action:
Remove the assignment statement from the group filter.

REP-01326
Trigger {0} writes to column {1} at the wrong frequency.

Category:
Other

Cause:
In a report trigger, an attempt was made to set the value of an Oracle Reports Builder column at the wrong frequency in the report. Only report-level columns or parameters can be referenced and set, and any page-dependent columns (that is, Reset At of Page) or columns that rely on page-dependent columns cannot be referenced or set.

Action:
Verify that the columns and parameters whose values are referenced or set are report-level columns and parameters.

REP-01327
Column {0} writes to column {1} at the wrong frequency.

Category:
Other

Cause:
In a formula column, an attempt was made to set the value of an Oracle Reports Builder column at the wrong frequency in the report. Only columns that are in the same group or in a higher group in the group hierarchy can be referenced and set. For example, a formula for a report-level column can only reference other report-level columns.

Action:
Verify that the columns whose values are referenced or set are in the same group or in a higher group in the group hierarchy.

REP-01328
A report containing ROWLABEL column {0} cannot be run in a non-trusted OS.

Category:
Other

Cause:
An attempt was made to run a report that requires a secure database while connected to a non-secure database.

Action:
Run the report while connected to a secure database.

REP-01329
Column {0} cannot be linked to column {1} because the child column is not a database column.

Category:
Other

Cause:
A data link was created in which the child column is a summary, formula, or placeholder column. Only database columns can be linked.

Action:
Create a data link using database columns.

REP-01330
Lexical parameter {0} in query {1} must not change column dependencies.

Category:
Other

Cause:
A lexical parameter was created that changes the number, type, or names of columns, or introduces new dependencies on computed columns or new bind references, when the report is run.

Action:
Change the lexical parameter so that it does not change columns or introduce new dependencies or bind references.

REP-01331
Column {0} cannot be linked to column {1} because the child column is determined by a lexical parameter.

Category:
Other

Cause:
A data link was created in which child column's value is determined by a lexical parameter, which is not allowed.

Action:
Replace the child column of the data link with another column.

REP-01332
Group filter for {0} cannot reference column {1}. It is not a valid database column or it depends on a related query.

Category:
Other

Cause:
A group filter was created that references a database column not in the group's query or in a query above it, or references a computed column that depends on an unrelated column.

Action:
Remove the offending reference from the group filter.

REP-01333
Unsupported layout: a matrix may not be inside another matrix.

Category:
Other

Cause:
A matrix layout was created nested within another matrix layout, which is not allowed.

Action:
Redesign the layout to avoid the nesting.

REP-01335
Variable rotated text {0} is treated as fixed/contract width.

Category:
Other

Cause:
The report contains a boilerplate text object that was rotated to an angle that is not a multiple of 90 degrees, although both Horizontal and Vertical Elasticity values were set to Variable or Expand. In this case, the Horizontal Elasticity is treated as Fixed (if Expand was specified) or Contract (if Variable was specified), and this warning is displayed.

Action:
Consider changing the Horizontal and Vertical Elasticity values for this boilerplate object.

REP-01336
The source of field {0} is page-level calculation {1}. {2}.

Category:
Other

Cause:
The specified field references a page summary owned by the named group, but there is no repeating frame for that group that surrounds the field.

Action:
Create a repeating frame whose Source is the named group to surround the field. If such a repeating frame already exists, extend it to enclose the field.

REP-01337
Boilerplate {3} references field {0}, whose source is page-level calculation {1}. {2}.

Category:
Other

Cause:
The specified boilerplate object references the specified field, whose Source is a page-level computation. However, there is no repeating frame (whose Source is the named group) surrounding the field.

Action:
Create a repeating frame whose Source is the named group to surround the field. If such a repeating frame already exists, extend it to enclose the field.

REP-01338
Column mode is not allowed on repeating frame {0}.

Category:
Other

Cause:
The Column Mode setting for a repeating frame does not satisfy either of the following conditions: Print Direction of Down and a Vertical Elasticity of Fixed. Print Direction of Across and a Horizontal Elasticity of Fixed.

Action:
Change the Print Direction or Vertical/Horizontal Elasticity of the repeating frame, or deactivate Column Mode.

REP-01339
Graph {0} is missing a data column specification.

Category:
Data

Cause:
A value was specified for the graph Query, but no columns were specified to be passed from the report to the graph document.

Action:
To pass no data from the report to the graph document, specify nothing for the graph Query and Source. To pass data, specify the columns to be passed in addition to the graph Query and Source.

REP-01340
Passed-in columns do not match report definition {0}.

Category:
Other

Cause:
Another component (for example, Oracle Forms) passed a query to Oracle Reports Builder and there is a mismatch between the columns passed and the columns expected by Oracle Reports Builder. Possible causes of this error include: Case 1: Oracle Reports Builder was expecting more or fewer columns than the number that was actually passed by the calling application. Case 2: The parameter list of the calling application described a column differently than what Oracle Reports Builder expected. For example, if the report's query selects a character column and the calling application assigns that column a date data type, this error is raised.

Action:
Take the following actions to correct this error: If Case 1: Ensure that the calling application is passing the same number of columns that Oracle Reports Builder expects. If Case 2: Ensure that the datatypes and names of the columns being passed by the calling application match the dataypes and names in the report.

REP-01341
Data truncation is possible in column {0}.

Category:
Data

Cause:
The database column's width in the report is defined to be less than its width in the database. This can occur when the columns in the database are updated subsequent to the creation of the report definition.

Action:
Force the query to be reparsed. One method is to type a space at the end of a line in the SELECT Statement and then accept the SQL Query Statement dialog box.

REP-01342
The type of the data link to query {0} is illegal for a non-Oracle server.

Category:
Data

Cause:
A data link was created with the START WITH clause and run while connected to a non-Oracle database. START WITH is only supported by Oracle.

Action:
Remove the data link that uses START WITH or connect to Oracle.

REP-01343
Button {0} is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01344
Button {0} has no action source file.

Category:
Other

Cause:
An action of Multimedia File was specified for the named button, but either a source file was not specified, or a source file was specified that does not exist.

Action:
Open the Property Inspector for the specified button and verify that a valid file was selected as source for the button action.

REP-01345
Button {0} has an invalid source column.

Category:
Other

Cause:
An action of Multimedia Column was specified for the named button, but either a source column was not specified, or an invalid source column was specified.

Action:
Open the Property Inspector for the specified button and verify that a valid column was selected as source for the button action.

REP-01346
Button {0} references source column {1} at the wrong frequency.

Category:
Other

Cause:
The column specified in the Property Inspector for the named button is in a group below that of the repeating frame that encloses the button.

Action:
Move the button into a repeating frame whose source group is at or above the group that contains the specified column. Otherwise, move the specified column into the enclosing repeating frame's group, if possible.

REP-01347
Button {0} has an invalid icon file.

Category:
Other

Cause:
Either an invalid file or a nonexistent file was specified as the icon file for the button face.

Action:
Ensure that the specified icon file exists and is of the proper format and uncorrupted.

REP-01348
The source column of field {0} is in sound or video format.

Category:
Other

Cause:
A column was specified containing sound or video as the source for a field, but fields cannot display sound and video.

Action:
Specify another column (not sound or video) as source of the field.

REP-01349
The PL/SQL action is missing from button {0}.

Category:
Other

Cause:
The PL/SQL trigger that serves as the specified button's action references a piece of PL/SQL that does not exist.

Action:
Debug the trigger and ensure that it references a valid program unit.

REP-01350
Output columns in action trigger {0} are not allowed.

Category:
Other

Cause:
The PL/SQL trigger that serves as a button action contains a bind variable that returns a value. A PL/SQL action trigger cannot return a value.

Action:
Remove the bind variable from the PL/SQL.

REP-01351
Icon {1} on button {0} cannot be found.

Category:
Other

Cause:
The icon specified as the button face for the named button cannot be found. The report will run, but the button will appear blank.

Action:
Open the Property Inspector for the named button and verify that the icon specified exists and is in the correct format, and that the path information is correct.

REP-01352
The fonts specified for this report cannot be found for the character set specified by NLS_LANG.

Category:
Other

Cause:
The NLS_LANG environment variable specifies a character set for which no font is available.

Action:
Select a font that exists in the character set specified by NLS_LANG. Alternatively, use the Font Alias file to force an available font to be used, instead of the one specified in the report.

REP-01353
The Web property of layout object {0} references field or column {1} at the wrong frequency.

Category:
Other

Cause:
One of the layout object properies (Bookmark, Action. Hyperlink, or Linktag) references a field or column, but the two objects are not located at the same frequency. For example, the layout

object is located within a repeating frame whose source is a different group to that the column is in.

Action:
Place the layout object in a repeating frame at the same frequency as the column object, or remove the reference.

REP-01354
The Web property of layout object {0} references a page-dependent field or column {1}.

Category:
Other

Cause:
One of the layout object properies (Bookmark, Action. Hyperlink, or Linktag) references a field or boilerplate object that has a reference to a page calculation or a total number of pages variable. Web properties may only reference columns and fields that are not based on page calculations.

Action:
Remove the Web property reference to the page-dependent field or column.

REP-01355
PL/SQL is missing from PL/SQL-based query {0}.

Category:
Other

Cause:
A PL/SQL based query was created, but no PL/SQL was entered for it.

Action:
Enter PL/SQL for the query.

REP-01356
A column link is not allowed for linking to PL/SQL-based query {0}.

Category:
Other

Cause:
An attempt was made to link a column to another column that is in PL/SQL-based query, which is not allowed.

Action:
Create group links and use the columns in the PL/SQL-based query as bind variables to set up intended column link conditions.

REP-01357
Auto foreign key column link creation is only for SQL queries.

Category:
Other

Cause:
A link was dragged between two queries to automatically create column links based on foreign key relationships. However, this can be done only between two SQL queries.

Action:
Drag a link between two SQL queries, or change the PL/SQL-based queries to SQL.

REP-01365
A column link is not allowed for linking to Express-based query {0}.

Category:
Other

Cause:
An attempt was made to link a column to another column that is an Express-based query, which is not allowed.

Action:
Create group links and use the columns in an Express-based query as bind variables to set up intended column link conditions.

REP-01366
The XML Settings of object {0} reference page-dependent field or column {1}.

Category:
Other

Cause:
One of the object's XML properties references a field that contains a page calculation or a total number of pages variable. XML Settings canot reference columns and fields that are based on page calculations.

Action:
Remove the XML Settings references to the page-dependent field or column.

REP-01367
The XML Settings of object {0} reference field or column {1} at the wrong frequency.

Category:
Other

Cause:
One of the object's XML properties references a field or column that has a different frequency than the object (for example, the column may be in a different group than the object referencing it).

Action:
Move the object such that it has the same frequency as the field or column (for example, place them in the same group) it references or remove the reference.

REP-01368
Group {0} in the graph settings is invalid.

Category:
Other

Cause:
In the graph object's graph settings, the src attribute is an invalid group name.

Action:
Ensure that value of the src attribute is a valid group name.

REP-01369
An internal error occurred caused by form field {0}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01370
Action {0} is unsupported.

Category:
Other

Cause:
The action specified against the form field is curently not supported.

Action:
Remove the action entry from the report definition.

REP-01371
Form field object {0} is unsupported.

Category:
Other

Cause:
This form field type is currently not supported by Oracle Reports.

Action:
Remove the Form Field element from the report definition.

REP-01372
The export value specified for {0} is invalid.

Category:
Other

Cause:
Either the export value is not specified or the export value is "off".

Action:
Specify a valid export value ("off" is a reserved word).

REP-01373
The validation and formatAndTreatment elements are not allowed for Form Field {0}.

Category:
Other

Cause:
The 'validation' or 'formatAndTreatment' element was specified for a Check Box and Radio Button.

Action:
Remove the 'validation' or 'formatAndTreatment' element for the Form Field object.

REP-01374
Font {0} is used to subset for the Form Field object {1}.

Category:
Other

Cause:
The font that is used to render a Form Field object was subsetted, which is not allowed.

Action:
Either remove the font entry in uifont.ali or modify the font name of the Form Field object to a font that is not subset.

REP-01400
coxr is not initialized.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01401
A fatal PL/SQL error occurred in program unit {2}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01402
An unhandled PL/SQL exception occurred in program unit {2}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01403
A PL/SQL procedure is suspended in program unit {2}.

Category:
Other

Cause:
A PL/SQL construct was suspended during execution or generation.

Action:
Debug and recompile the PL/SQL constructs.

REP-01404
PL/SQL compilation failed.

Category:
Other

Cause:
In generating the report, PL/SQL compilation failed.

Action:
Debug the PL/SQL constructs.

REP-01405
The PL/DQL code is not executable.

Category:
Other

Cause:
A PL/SQL construct did not compile properly or could not be executed.

Action:
Debug the PL/SQL constructs.

REP-01406
Parameterized code cannot be run directly.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01408
The PL/SQL cannot be initialized.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01409
Expected IS after PROCEDURE cannot be found.

Category:
Other

Cause:
A PL/SQL syntax error occurred.

Action:
Correct the PL/SQL procedure in trigger/program unit and compile.

REP-01410
An error occurred executing a PL/SQL filter in program unit {2}.

Category:
Other

Cause:
A PL/SQL syntax error occurred.

Action:
Correct the PL/SQL procedure in trigger/program unit and compile.

REP-01411
An error occurred executing PL/SQL formula in program unit {2}.

Category:
Other

Cause:
A PL/SQL syntax error occurred.

Action:
Correct the PL/SQL procedure in program unit of formula column or trigger. Verify the variable declarations and usage.

REP-01412
PL/SQL function {2} returned an invalid value or no value.

Category:
Other

Cause:
The report contains a PL/SQL function that does not specify a return value (for example, a format trigger that does not return TRUE or FALSE).

Action:
Verify that the function includes a return statement for every code path.

REP-01414
A library unit to run cannot be found in program unit {2}.

Category:
Other

Cause:
This is most likely an abnormal condition.

Action:
Check the PL/SQL code and recompile it. If this error recurs, contact Oracle Support Services.

REP-01415
An unknown user exit {0} was encountered in program unit {2}.

Category:
Other

Cause:
A user exit was called, but it was not found.

Action:
Verify the correct name for the user exit and that it has been compiled and linked.

REP-01416
An error occurred in user exit {0} in program unit {2}. {1}.

Category:
Other

Cause:
An error occurred in a user exit. Possible errors: a reference to an unknown column, a truncated column value, unretrievable PL/SQL source, or the user exit was not found.

Action:
Based on the submessage, debug the user exit. Veirfy columns references are valid and the PL/SQL code and user exit are accessible.

REP-01417
An invalid integer argument was passed to procedure {0} in program unit {2}.

Category:
Other

Cause:
The packaged procedure referenced expected an integer for an argument, but it was not specified.

Action:
Verify that the PL/SQL that references the packaged procedure correctly passes it an integer. For more information about PL/SQL packaged procedures, see the Oracle Reports online help.

REP-01418
Null arguments were passed to procedure {0} in program unit {2}.

Category:
Other

Cause:
The exception SRW.NULL_ARGUMENTS was raised, either by a user-defined PL/SQL subprogram, or because a packaged subprogram was passed one or more null arguments.

Action:
Check any PL/SQL code that might raise this exception. Also, check the argument list that is passed to the specified packaged subprogram.

REP-01419
The PL/SQL program was aborted in program unit {2}.

Category:
Other

Cause:
A PL/SQL construct had a fatal error and was aborted.

Action:
Check the PL/SQL constructs for errors.

REP-01420
The PL/SQL program raised a program error in program unit {2}.

Category:
Other

Cause:
The exception SRW.PROGRAM_ERROR was raised, either by a user-defined PL/SQL subprogram, or because of an abnormal condition.

Action:
Check any PL/SQL code that might raise this exception. If no PL/SQL raised the exception, contact Oracle Support Services.

REP-01421
A column of the wrong type was manipulated in procedure {0} in program unit {2}.

Category:
Other

Cause:
The data type of the column whose name was passed to a packaged procedure is not the correct data type for the packaged procedure (for example, the packaged procedure was expecting a column of Character data type and it was passed a column of another data type).

Action:
Debug the PL/SQL that references packaged procedures and ensure that the packaged procedure is passed the name of a column of the correct data type. Also check the syntax of the packaged procedure to ensure that its is referenced properly.

REP-01422
A procedure by this name already exists.

Category:
Other

Cause:
An attempt was made to create a new PL/SQL procedure with the same name as an existing PL/SQL procedure.

Action:
Change the name of the new procedure or change the name of the existing procedure.

REP-01423
Maximum rows of a query cannot be set after the query started executing in program unit {2}.

Category:
Other

Cause:
SRW.SET_MAX_ROW was used to reduce the number of rows fetched by a query. However, SRW.SET_MAX_ROW was called after the query was already fetched.

Action:
Move SRW.SET_MAX_ROW to the Before Report trigger.

REP-01424
An internal error occurred while executing procedure {0} in program unit {2}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01425
An error occurred running DO_SQL package in program unit {2}: {0}.

Category:
Other

Cause:
An error occurred while Oracle Reports Builder was executing an SRW.DO_SQL call. Embedded in this message is an Oracle Reports Builder message and, possibly, an Oracle error message describing the exact error that occurred.

Action:
Errors in SRW.DO_SQL are most often the result of a SQL error. Refer to the SQL Language Reference Manual and verify that the SQL statement in the SRW.DO_SQL call is correct.

REP-01426
Procedure {0} was running from incorrect context in program unit {2}.

Category:
Other

Cause:
An attempt was made to call the named packaged procedure from an invalid area. For example, SRW.SET_ATTR cannot be called from a formula.

Action:
Modify the PL/SQL code so that it does not call the packaged procedure from that context.

REP-01427
A nonexistent query name was referenced in procedure {0} in program unit {2}.

Category:
Other

Cause:
A call was made to the SRW.SET_MAXROW procedure in a Before Report trigger, but the query referenced in the procedure call does not exist.

Action:
Change the call to the SRW.SET_MAXROW procedure so that it references an existing query in the report.

REP-01428
An error occurred while running procedure {0} in program unit {2}.

Category:
Other

Cause:
The exception SRW.RUN_REPORT_FAILURE was raised, either by a user-defined PL/SQL subprogram, or because of an abnormal condition after SRW.RUN_REPORT was called.

Action:
Check any PL/SQL code that might raise this exception. If no PL/SQL raised the exception, check the command line string passed to SRW.RUN_REPORT. Verify that BATCH=YES, that the specified report exists, and that all parameter values are correct.

REP-01429
Procedure {0} cannot be invoked with BATCH=NO in program unit {2}.

Category:
Other

Cause:
A call was made to the SRW.RUN_REPORT procedure with a command line string containing BATCH=NO, which is not allowed.

Action:
Remove BATCH=NO from the SRW.RUN_REPORT command string.

REP-01430
A REP file for report {0} cannot be created: compilation errors found.

Category:
Other

Cause:
There is an error in the PL/SQL in the report to be converted.

Action:
Open the report and debug the PL/SQL.

REP-01433
An error occurred running user exit {0} in program unit {2}.

Category:
Other

Cause:
While running the user exit named in the message, an error occurred.

Action:
Debug the user exit and ensure that it is linked.

REP-01434
Procedure {0} cannot be invoked with a user ID in program unit {2}.

Category:
Other

Cause:
A call was included to the SRW.RUN_REPORT procedure with a command line string containing a userid/password, which is not allowed.

Action:
Remove the userid/password from the SRW.RUN_REPORT command string.

REP-01435
The value of column {0} was truncated in program unit {2}.

Category:
Other

Cause:
A column (for example, a placeholder) was assigned a value larger than its width could contain, raising the SRW.TRUNCATED_VALUE exception. The exception was not handled, raising this error.

Action:
Make the column wide enough to contain the assigned value, or handle the exception in the PL/SQL source.

REP-01436
The PL/SQL references an object that is not in the scope in program unit {2}.

Category:
Other

Cause:
In a parameter's Validation Trigger field, PL/SQL source referenced a report column, which is not allowed.

Action:
Remove the reference to the report column from the parameter's Validation Trigger.

REP-01437
A run time error in the PL/SQL development environment (DE).

Category:
Other

Cause:
This is most likely an abnormal condition.

Action:
Refer to the accompanying development environment error message for details on the problem. For assistance, contact Oracle Support Services.

REP-01438
The GETREF function parameter {0} must be of type LONG, LONG RAW, or RAW.

Category:
Other

Cause:
The second parameter in a CDE_MM.GET_REF call specifies a column that is not of type LONG, LONG RAW, or RAW.

Action:
Change the second parameter to specify a column of the correct type.

REP-01440
An unknown column name was passed to {0} in program unit {2}.

Category:
Other

Cause:
A column name specified in the named program unit in one of the triggers is invalid.

Action:
Verify the column name is correct.

REP-01441
A column value was not available for {0} in program unit {2}.

Category:
Other

Cause:
A column name specified in the named program unit in one of the triggers is not available.

Action:
Verify the column value is correct.

REP-01442
Column value {0} cannot be set in program unit {2}.

Category:
Other

Cause:
A value is not settable for this column.

Action:
Verify the procedure is correct.

REP-01443
Column value {0} is invalid in program unit {2}.

Category:
Other

Cause:
A column value specified in the named program unit in one of the triggers is invalid.

Action:
Verify the column value is correct.

REP-01444
No more rows exist in the group handle.

Category:
Other

Cause:
SRW.GH_NEXT() is called when the group handle is already at the last row.

Action:
Catch a SRW.NO_DATA_FOUND exception in PL/SQL.

REP-01445
The JAVA class cannot be found.

Category:
Other

Cause:
The requested class could not be located within the Reports classpath.

Action:
Ensure that the class is correctly specified (for example, java/lang/String) and that the class is in the Reports classpath specified in the REPORTS_CLASSPATH environment variable.

REP-01446
The JAVA method cannot be found.

Category:
Other

Cause:
The requested method could not be located within in the specified class.

Action:
Ensure that the method exists within the specified class and has the correct signature: '(Ljava/lang/String;)Ljava/lang/String;'.

REP-01447
A JAVA exception was encountered.

Category:
Other

Cause:
An error occurred attempting to start the JVM and access the requested Java class and method.

Action:
Check the JVM install and environment.

REP-01448
The data model group passed to SRW.GH_CREATE() does not exist.

Category:
Data

Cause:
The group name parameter of SRW.GH_CREATE() is invalid.

Action:
Ensure that the group name is correctly specified. Catch the SRW.UNKNOWN_GROUP exception in PL/SQL.

REP-01508
Cross Product: value of calculation cannot be found.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01510
Group Manager: unable to compute column {0}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01516
Reset At Page is an invalid option for column {0} in Web-based reports.

Category:
Other

Cause:
A column in the report layout has Reset At Page, which is invalid for Web-based reports.

Action:
Specify Reset At for either a group or report for Web-based reports.

REP-01517
Column {0} references column {1}, which has incompatible frequency.

Category:
Other

Cause:
A column in the data model references another column (for example, in the Formula field) in the data model, but the two columns are assigned to incompatible groups. For example, if a formula column with a Group of Report referenced a column with a Group of G_Emp, this error is raised.

Action:
Remove the column reference, or assign the referencing column to a group that is compatible with the group of the referenced column.

REP-01518
Group Manager: internal error {0} occurred while processing group {1}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01607
Record Manager: the source of report level column {0} is not available.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01610
Record Manager: a query with internal joins has Maximum Number of Rows set.

Category:
Other

Cause:
SRW.SET_MAXROW was probably used to set Maximum Number of Rows on the cell query of a multiquery cross product.

Action:
Remove the call to SRW.SET_MAXROW for the cell query.

REP-01760
Error Utility: internal error #1 occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01761
Internal error {0} occurred while processing {2} {1}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01762
Internal error {0} occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01780
Stack utility: an error occurred during allocation.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01781
Stack utility: an error occurred during push.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01782
Stack utility: an error occurred during pop.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01783
Stack utility: an attempt was made to pop an empty stack.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01800
A formatter error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01801
An unknown file type was encountered for a Read from File field.

Category:
Other

Cause:
An attempt was made to create a file column, but the file type entered was invalid.

Action:
Display the list of values and pick a valid file type.

REP-01802
Contents of a field cannot be read from a text file.

Category:
Other

Cause:
Read from File was selected for a column, but Oracle Reports Builder could not find the files pointed to by the column. The possible causes of this error include the following: Case 1: The files do not exist. Case 2: The necessary privileges to access the files are not granted. Case 3: A system error made it impossible to find the files.

Action:
Take the following actions to correct this error: If Case 1: Uncheck Read from File or create the necessary files. If Case 2: Update privileges, if possible. If Case 3: Consult the operating system documentation or contact the system administrator.

REP-01803
Destination file {0} cannot be opened.

Category:
Other

Cause:
The destination file specified for the report could not be opened.

Action:
Consult the operating system documentation or contact the system administrator.

REP-01804
Printer definition file {0} cannot be opened.

Category:
Other

Cause:
The printer definition file for the specified printer could not be opened.

Action:
Consult the operating system documentation or contact the system administrator.

REP-01805
Mail text file {0} cannot be opened.

Category:
Other

Cause:
An attempt was made to send the report output to a mail message, but the file for the message could not be opened.

Action:
Consult the Oracle*Mail documentation or contact Oracle Support Services.

REP-01806
Mail command file {0} cannot be opened.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01807
The mail report command failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01808
The print command file cannot be opened.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01809
The print report command failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01810
The Oracle Reports Builder ASCII Driver will be used to run a character report.

Category:
Other

Cause:
An attempt was made to print a character-mode report to a printer or a file using either a PostScript driver or the Microsoft Windows Generic Text driver.

Action:
No action necessary.

REP-01811
An error occurred while generating a graph.

Category:
Other

Cause:
Oracle Reports Builder called Graphics Runtime to generate a graph, but no graph was created.

Action:
Verify that the named graph document exists and will run.

REP-01812
Too many pages formatted. There is either too much data or an error in the report's definition.

Category:
Data

Cause:
The possible causes of this error include the following: Case 1: A user-defined limit set to catch too much data has been reached. Case 2: An error in the report definition has been reached.

Action:
Take the following actions to correct this error: If Case 1: Abort running the program. Check the value of PAGE_LIMIT in the PRODUCT_PROFILE table. Ensure that it is either '0', which means the user is allowed to format an unlimited number of pages, or some value sufficiently large to enable the user to format the report. If Case 2: Debug the report in the Report Editor.

REP-01813
Object {0} is too large to fit in a matrix cell.

Category:
Other

Cause:
The data fetched into a matrix cell exceeds the capacity of the cell. For example, the cell may contain a variable field, and the data may be longer than expected.

Action:
Either enlarge the matrix cells until they are able to contain the data fetched into them, or redefine the data.

REP-01814
The report cannot be formatted. Object {1} cannot fit within location {0}.

Category:
Other

Cause:
The referenced object is causing the most recently formatted page to start with exactly the same state as the previous page. Formatting will therefore cycle until abnormally terminated. Possible causes of this error include: Case 1: An object whose Print Condition type is All overflows to the next page. Case 2: An object whose sizing is Variable or Expand does not appear to extend beyond page boundaries in the Paper Layout editor but does when the report is formatted. Case 3: A repeating frame does not appear to extend beyond page boundaries in the Paper Layout editor but does when the report is formatted.

Action:
Using the referenced object as a guide, examine the report layout for objects that may extend beyond page boundaries. Note: The object referenced in the message is the object that extends beyond the boundary. This object may be pushed beyond the boundary by another object, and this second object may need modification.

REP-01815
A bad Oracle Number was encountered.

Category:
Other

Cause:
A formula providing the value of a column failed to specify any value.

Action:
Debug any formulas in the report columns and ensure that each formula specifies a value where necessary.

REP-01816
No value was specified for COPIES, and no output was created.

Category:
Other

Cause:
In the Runtime Parameter Form or the Print Job dialog box, zero (0) copies was specified.

Action:
Specify a value of one or more copies.

REP-01817
The start page occurs after the end page. No pages were generated.

Category:
Other

Cause:
In the Print Job dialog box, a starting page number was specified that is greater than the ending page number.

Action:
Change either the starting page number or the ending page number such that the starting number is less than the ending number.

REP-01818
Data in image format could not be read.

Category:
Data

Cause:
Possible causes of this error include: Case 1: An attempt was made to read a file or database column as containing an image, but the file or column's contents are of the wrong format. Case 2: The width of the Oracle Reports Builder column specified may be truncating the image because it is too small. Case 3: REPORTS_DEFAULT_DISPLAY is set to YES and the image format used is not supported.

Action:
Take the following actions to correct this error: If Case 1: Verify that the file or column specified contains an image in a valid format. If Case 2: Change the width of the Oracle Reports Builder column so that it is large enough to display the image. If Case 3: Verify that the image format is one of the supported formats: GIF, JPEG, JPG, PNG, BMP.

REP-01819
Filename {0} is longer than the platform maximum of {1} characters.

Category:
Other

Cause:
A name was specified for a file that is longer than the platform-allowed maximum. This is most likely to occur when accessing a file using Read from File, and the file name in the database is too long.

Action:
Verify that the database is not corrupted, or run the report on a platform that accepts filenames of the specified length.

REP-01820
The Oracle Reports Builder ASCII Driver cannot be used to run a bitmap report.

Category:
Other

Cause:
An attempt was made to print a bitmapped report when the Oracle Reports Builder ASCII Driver is the default printer.

Action:
Select a different printer, then print the report.

REP-01825
The Before Report trigger returned FALSE.

Category:
Other

Cause:
The report includes a Before Report trigger that returned a value of FALSE rather than TRUE. When a trigger returns a value of FALSE, report formatting stops.

Action:
Verify that the report trigger is meant to return a value of FALSE.

REP-01826
The Between Page trigger returned FALSE.

Category:
Other

Cause:
The report includes a Between Page trigger that returned a value of FALSE rather than TRUE. When a trigger returns a value of FALSE, report formatting stops.

Action:
Verify that the report trigger is meant to return a value of FALSE.

REP-01827
Parentheses in the format mask do not balance.

Category:
Other

Cause:
Unmatched parenthesis exist in the format mask.

Action:
Edit the format mask and insert the necessary parenthesis.

REP-01828
A format mask may contain at most one set of parentheses.

Category:
Other

Cause:
More than one set of parentheses was used in the format mask.

Action:
Use only one set of parentheses in the format mask.

REP-01829
Left parenthesis must precede right parenthesis in a format mask.

Category:
Other

Cause:
The order of the parentheses was reversed in the format mask; that is, the right, or close, parenthesis was used before the left, or open parenthesis.

Action:
Edit the format mask and reverse the order of the parentheses.

REP-01830
The Exponent field in a format mask must contain exactly 4 Es.

Category:
Other

Cause:
The scientific notation specified for the field contained too many or too few E's.

Action:
Enter the format mask with four E's. To have extra E's appear in the output, put them in quotation marks (").

REP-01831
A closing quotation mark in format mask is missing.

Category:
Other

Cause:
An opening quotation mark (") was entered before the string in the format mask, but not a closing one. The possible causes of this error include the following: Case 1: No closing quotation mark was entered after the string. Case 2: One quotation mark was entered within the quotation marks that begin and end the string.

Action:
Take the following actions to correct this error: If Case 1: Add an ending quotation mark after the string. If Case 2: Enter another quotation mark next to the quotation mark inside the string.

REP-01832
Illegal character {0} was encountered in the format mask.

Category:
Other

Cause:
A character was entered in a format mask that is not valid for format masks.

Action:
Delete the illegal character. For more information, see the date and time format mask information in the Building Reports manual.

REP-01833
A format mask must contain at least one digit.

Category:
Other

Cause:
The format mask entered contains no digits. At least one token in the mask must represent a digit.

Action:
Enter a token in the format mask that represents a digit. The tokens that represent digits are 0, 9, *, and S. For more information, see the date and time format mask information in the Building Reports manual.

REP-01834
A format mask may contain at most one < character.

Category:
Other

Cause:
The format mask included two left angle brackets (<<). The angle brackets need not be entered sequentially to cause the error.

Action:
Delete the extra left angle bracket or place it inside quotation marks (") as part of a string if it should appear in the output.

REP-01835
A format mask may contain at most one > character.

Category:
Other

Cause:
The format mask included two right angle brackets (>>). The angle brackets need not be entered sequentially to cause the error.

Action:
Delete the extra right angle bracket or place it inside quotation marks (") as part of a string if it should appear in the output.

REP-01836
A left angle bracket must come before a right angle bracket in a format mask.

Category:
Other

Cause:
The left angle bracket (<) must come before the right angle bracket (>) in a format mask.

Action:
Ensure that all angle brackets that are to appear in the output are placed inside quotation marks ("). For the angle brackets that delineate the beginning and ending of the decimal aligned region, ensure that the left angle bracket precedes the right angle bracket in the format mask.

REP-01837
A format mask may contain at most one decimal point.

Category:
Other

Cause:
A format mask was entered with multiple decimal points.

Action:
To have extra decimal points appear in the output, place them in quotation marks ("). Remove any extra decimal points outside of quotation marks.

REP-01838
A format mask may contain at most one scale point.

Category:
Other

Cause:
The token V was entered more than once within the format mask.

Action:
To have extra V's appear in the output, place them in quotation marks ("). Otherwise, delete the V's until there is only one in the format mask.

REP-01839
A comma is not allowed before the first digit in a format mask.

Category:
Other

Cause:
A comma (,) was entered before the first digit in the format mask, which is illegal.

Action:
To have a comma appear before the digits in the output, place it in quotation marks (") as a string. Otherwise, delete the comma.

REP-01840
A comma is not allowed after the last digit in a format mask.

Category:
Other

Cause:
A comma (,) was entered after the last digit in the format mask, which is illegal.

Action:
To have a comma appear after the digits in the output, place it in quotation marks (") as a string. Otherwise, delete the comma.

REP-01841
A comma is not allowed after the decimal point in a format mask.

Category:
Other

Cause:
A comma (,) was entered after the decimal point in the format mask.

Action:
To have a comma appear after the decimal point in the output, place it in quotation marks (") as a string. Otherwise, delete the comma.

REP-01842
A format mask may contain at most one exponent field.

Category:
Other

Cause:
The token EEEE was entered more than once within the format mask. This token may be entered only once per format mask.

Action:
To have the extra E's appear in the output, place them in quotation marks ("). Otherwise, delete the extra EEEE tokens until there is only one in the format mask.

REP-01843
Format masks with exponent fields must have exactly one digit before the decimal point.

Category:
Other

Cause:
A scientific notation format mask was entered that had no digits or more than one digit to the left of the decimal point.

Action:
Delete digits or add a digit until there is only one to the left of the decimal point.

REP-01844
An internal error occurred: Bad index in a flexible array.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01845
The decimal point must come between the angle brackets in a format mask.

Category:
Other

Cause:
A decimal point was placed outside the left and right angle brackets (\< and \>) of the format mask.

Action:
Edit the format mask to either remove the decimal point or place it between the brackets.

REP-01846
A Roman numeral format mask must be simply \"RN\" or \"rn\".

Category:
Other

Cause:
A Roman numeral format mask token (RN or rn) was specified, along with other format mask tokens.

Action:
To format the values as Roman numerals, eliminate all format mask tokens except RN or rn from Format Mask. Otherwise, do not use the RN or rn token.

REP-01847
The current process failed while trying to set up for printing.

Category:
Process

Cause:
An attempt was made to print a report. The possible causes of this error include the following: Case 1: In the Runtime Parameter Form or on the command line, Printer was specified for DESTYPE, but an invalid printer name was specified for DESNAME. Case 2: The report that was executed in turn executes a second report using SRW.RUN_REPORT. DESTYPE for both reports is set to either File or Printer, but the first report must be run to the screen.

Action:
Take the following actions to correct this error: If Case 1: Retry the operation, specifying a valid printer name for DESNAME. If Case 2: Change the DESTYPE for the first report to Screen or Previewer and run it again.

REP-01848
The current process failed while trying to begin printing.

Category:
Process

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01849
The current process failed while printing.

Category:
Process

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01850
An error occurred in column {0} of line {1} of printer definition file {2}: End of file reached inside quoted string.

Category:
Other

Cause:
The printer definition file contains a quoted string that was not ended with a quote before the end of the file.

Action:
Use the location specified in the error message to locate the error and add the end quote to the quoted string in the printer definition file.

REP-01851
An error occurred in column {0} of line {1} of printer definition file {2}: String is longer than {3} characters.

Category:
Other

Cause:
A string in the printer definition file is longer than the maximum number of allowable characters.

Action:
Reduce the length of the string.

REP-01852
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
An incorrect keyword is included in the printer definition file.

Action:
Verify the printer definition file syntax.

REP-01853
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
An incorrect keyword was found in the printer definition file.

Action:
Verify the printer definition file syntax.

REP-01854
An error occurred in column {0} of line {1} of printer definition file {2}: Invalid control character {3}.

Category:
Other

Cause:
An invalid control character was found in the printer definition file.

Action:
Replace or remove the invalid control character in the printer definition file.

REP-01855
An error occurred in column {0} of line {1} of printer definition file {2}: Unknown character {3}.

Category:
Other

Cause:
An unknown character was found in the printer definition file.

Action:
Replace or remove the unknown character in the printer definition file.

REP-01856
An error occurred in column {0} of line {1} of printer definition file {2}: {3} is not a valid ASCII character.

Category:
Other

Cause:
An invalid ASCII character appears in the printer definition file.

Action:
Replace or remove the invalid ASCII character in the printer definition file.

REP-01857
An error occurred in column {0} of line {1} of printer definition file {2} following {3}.

Category:
Other

Cause:
An unmatched parenthesis was found in the printer definition file.

Action:
Edit the printer definition file and insert the necessary parenthesis.

REP-01858
An error occurred in column {0} of line {1} of printer definition file {2}: octal {3} is not a valid ASCII character.

Category:
Other

Cause:
The octal code for an ASCII character in the printer definition file is incorrect.

Action:
Edit the printer definition file and correct the code for the ASCII character.

REP-01859
An error occurred in column {0} of line {1} of printer definition file {2}: hex {3} is not a valid ASCII character.

Category:
Other

Cause:
The hex code for an ASCII character in the printer definition file in incorrect.

Action:
Edit the printer definition file and correct the code for the ASCII character.

REP-01860
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains an incomplete code string.

Action:
Edit the printer definition file and complete the code string with the appropriate word.

REP-01861
An error occurred in column {0} line {1} of file {2}.

Category:
Other

Cause:
The printer definition file contains an incomplete "box" code string.

Action:
Edit the printer definition file and complete the "box" code string with the appropriate word.

REP-01862
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file does not include the required code "printer".

Action:
Edit the printer definition file and add the required code "printer" followed by the name of the printer in a quoted string, preferably on the first line of the printer definition file.

REP-01863
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains the name of the printer after the "printer" code, but the name does not appear in a quoted string.

Action:
Edit the printer definition file and place quotation marks (") around the name of the printer after the "printer" code.

REP-01864
An error occurred in column {0} line {1} of file {2}.

Category:
Other

Cause:
The printer definition file does not contain any of the code words expected in a printer definition file.

Action:
Edit the printer definition file and add the code words that are missing.

REP-01865
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains the "width" code, but no number specifying the width of the report appears after it.

Action:
Edit the printer definition file and insert a number specifying the width of the report after the "width" code.

REP-01866
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains the "height" code, but no number specifying the height of the report appears after it.

Action:
Edit the printer definition file and insert a number specifying the height of the report after the "height" code.

REP-01867
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains the word "before" but not the accompanying word "report".

Action:
Edit the printer definition file to include a complete "before report" entry.

REP-01868
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains the word "between" but not the accompanying word "pages".

Action:
Edit the printer definition file to include a complete "between pages" entry.

REP-01869
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file (for a multipage report) contains the code word "after" but not the accompanying word "report".

Action:
Edit the printer definition file to include a complete "after report" entry.

REP-01870
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains the "code" code with a user-defined string, but the string is not enclosed within quotation marks.

Action:
Edit the printer definition file and enclose the "code" user-defined string with quotation marks.

REP-01871
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains a generalized string using "dec", but "dec" is not followed with a left parenthesis.

Action:
Edit the printer definition file and add parentheses around the value following "dec".

REP-01872
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains a generalized string (for example, dec or octal), but no value follows the right parenthesis.

Action:
Edit the printer definition file and add a value between the parentheses in the generalized string.

REP-01873
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains a generalized string using "octal", but "octal" is not followed with a left parenthesis.

Action:
Edit the printer definition file and add parentheses around the value following "octal".

REP-01874
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains a generalized string (for example, dec or octal), but no value follows the left parenthesis.

Action:
Edit the printer definition file and add a value between the parentheses in the generalized string.

REP-01875
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains a generalized string using "hex", but "hex" is not followed with a left parenthesis.

Action:
Edit the printer definition file and add parentheses around the value following "hex".

REP-01876
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains a generalized string (for example, dec or octal), but no value follows the left parenthesis.

Action:
Edit the printer definition file and add a value between the parentheses in the generalized string.

REP-01877
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains a generalized string using "^", but no control character follows the "^".

Action:
Edit the printer definition file and add a control character after "^".

REP-01878
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains a keyword and generalized string (for example, after report or before report), but no left parenthesis follows the word "control".

Action:
Edit the printer definition file and add a left parenthesis following the word "control".

REP-01879
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains a keyword and generalized string (for example, after report or before report), but no control character follows the left parenthesis.

Action:
Edit the printer definition file and add a control character between the parentheses after the word "control".

REP-01880
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains the "box" code string, but the drawing string specified between quotation marks is more than one character long.

Action:
Edit the printer definition file, making sure that one and only one character is specified as a drawing string.

REP-01881
An error occurred in column {0} of line {1} of printer definition file {2}.

Category:
Other

Cause:
The printer definition file contains the "box" code string, but no drawing string is specified.

Action:
Edit the printer definition file and specify a drawing string.

REP-01882
An error occurred in column {0} line {1} of file {2}.

Category:
Other

Cause:
The printer definition file contains the "box" code string, but the following required word (one of 'horizontal', 'vertical', 'top', 'center', or 'bottom') is not specified.

Action:
Edit the printer definition file and add the appropriate required word.

REP-01883
Unexpected end of printer definition file was reached.

Category:
Other

Cause:
Oracle Reports Builder was able to open the printer definition file, but an error occurred while reading it.

Action:
Verify that the correct printer definition file is specified. Also, check the contents of the printer definition file. Edit the file if necessary.

REP-01884
A hang occurred while sending output.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01885
Output could not be sent to the printer.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-01886
Expected I after M in the format mask cannot be found.

Category:
Other

Cause:
The M entered in a format mask was not followed by I. The only token that begins with M is the MI token.

Action:
To use the MI token, enter an I after the M. To have the character M appear in the output, place it inside double quotation marks ("). Otherwise, delete the M from Format Mask.

REP-01887
Expected R after P in the format mask cannot be found.

Category:
Other

Cause:
The P entered in a format mask was not followed by R. The only token that begins with P is the PR token.

Action:
To use the PR token, enter an R after the P. To have the character P appear in the output, place it inside double quotation marks ("). Otherwise, delete the P from Format Mask.

REP-01888
Only one sign token is allowed.

Category:
Other

Cause:
More than one sign token was entered in a format mask.

Action:
Delete all sign tokens but one from the format mask.

REP-01889
A trailing sign token must be at the end.

Category:
Other

Cause:
A sign token was not placed at the end of the format mask.

Action:
Place the sign token (for example, MI, PR, DB, and CR) at the end of the format mask.

REP-01890
The S token must be at the beginning or end.

Category:
Other

Cause:
The S token was not placed at the beginning or the end of the format mask.

Action:
Place the S token at the beginning or the end of the format mask or delete it.

REP-01891
Parentheses tokens must surround other tokens.

Category:
Other

Cause:
The parentheses tokens do not surround all other tokens in the format mask.

Action:
Place the parentheses around all of the other tokens in the format mask.

REP-01892
The destype specified is not supported for pdf or html.

Category:
Other

Cause:
An invalid destination type (destype) was specified for pdf or html output.

Action:
Specify a destination type (destype) of file or cache for pdf or html output.

REP-01893
The destype specified is not supported on this platform.

Category:
Other

Cause:
An invalid destination type (destype) was specified for the operating system (for example, Sysout, while running on Microsoft Windows).

Action:
Specify a valid destination type.

REP-01894
The report definition was modified during the current run. No new pages will be generated.

Category:
Other

Cause:
While previewing a report (using Oracle Reports Builder), the report's definition was modified, and then an attempt was made to view additional pages from the Previewer. Oracle Reports Builder cannot guarantee that all of the information used at runtime is still present, so formatting is halted.

Action:
No action required.

REP-01895
A date formatting error occurred while processing field {0}.

Category:
Other

Cause:
Oracle Reports Builder could not format the specified date field.

Action:
Check the format mask of the specified date field.

REP-01896
An error occurred in column {0} of line {1} of printer definition file {2}: Expected backspace or overstrike to follow hilight.

Category:
Other

Cause:
The specified printer definition file contains the 'hilight' setting, but the setting was not completed properly.

Action:
Add either 'overstrike' or 'backspace <sequence>' after 'hilight'.

REP-01897
An error occurred in column {0} of line {1} of printer definition file {2}: Non-numeric user-defined printer codes are not supported.

Category:
Other

Cause:
The specified printer definition file contains a user-defined printer code that is not a number.

Action:
Change the user-defined printer code to a number.

REP-01898
An error occurred in column {0} of line {1} of printer definition file {2}: Hilight setting can only be defined once.

Category:
Other

Cause:
The specified printer definition file contains more than one hilight setting.

Action:
Remove all but one of the hilight settings from the printer definition file.

REP-01899
Graphics Display or Icon cannot be converted to .gif format - image skipped.

Category:
Other

Cause:
Oracle Reports Builder was unable to convert an embedded Graphics Display or icon to a GIF format for displaying within an HTML document. This only occurs when Oracle Reports Builder cannot access a window system in order to draw the image.

Action:
Run the report using the bitmap executable under a windowing system to allow Oracle Reports Builder access to a display.

REP-01920
Character mode runtime is incompatible with DESFORMAT of PDF, HTML, HTMLCSS, SPREADSHEET, or RTF.

Category:
Other

Cause:
An attempt was made to run a report with a destination format of PDF, HTML, HTMLCSS, SPREADSHEET, or RTF. These formats are only available when running in a bitmap environment and producing a bitmap output.

Action:
Rerun the report with a bitmap executable or set MODE=BITMAP if already running with a bitmap executable.

REP-01921
Input printer tray {0} is not available on the selected printer.

Category:
Other

Cause:
An attempt was made to alter the input printer tray but the name of the tray specified is not available on the currently selected printer.

Action:
Change the selected printer to one that supports the specified tray or alter the tray name to one supported by the specified printer. Use Page Setup to view the list of printer trays supported by the printer.

REP-01922
A PDF compression error was encountered.

Category:
Other

Cause:
The compression engine failed compressing this page.

Action:
Turn off compression for this report by specifying PDFCOMP=NO on command line.

REP-01923
A PDF Font Embed error was encountered.

Category:
Other

Cause:
The font specified for embedding into the PDF document cannot be found or is invalid.

Action:
The [PDF:Embed] section must be present in the uifont.ali file. Check to ensure that the entry of font in the uifont.ali is syntactically correct. Verify that the location of font files is added to REPORTS_PATH in the registry/environment variable.

REP-01924
Font file {0} cannot be found.

Category:
Other

Cause:
The font file specified in UIFONT.ALI is not found.

Action:
Verify that the font file exists in REPORTS_PATH.

REP-01925
Font file {0} is invalid.

Category:
Other

Cause:
The font file appears to be corrupt or invalid.

Action:
Ensure the specified file is a valid font file.

REP-01926
Identical name {0} was specified for dissimilar form field types {1} and {2}.

Category:
Other

Cause:
The name specified for a form field conflicts with an existing form field of different type.

Action:
Select a new name for one of the form fields. Change the type of the form field to match that of the existing form field.

REP-01927
Cannot print document or generate output in printer format because the printer is offline or paused.

Category:
Other

Cause:
When destination type is printer or format is printer name, running request fails if the printer is offline or paused.

Action:
Bring the printer online and try again.

REP-01940
An error occurred in column {0} line {1} of file {2}: Expected visualorder, logicalorder, contextualshaping, contextuallayout, multibyte, or pcharset.

Category:
Other

Cause:
The printer definition file contains the 'nls' code string, but the required word (one of 'visualorder', 'logicalorder', 'contextualshaping', 'contextuallayout', 'multibyte', or 'pcharset') is not specified.

Action:
Edit the printer definition file and add the required word.

REP-01941
An error occurred in column {0} line {1} of file {2}: Expected yes or no.

Category:
Other

Cause:
The printer definition file contains 'visualorder', 'logicalorder', 'contextualshaping', 'contextuallayout', 'multibyte', or 'pcharset' code string, but the required word (either 'yes' or 'no) is not specified.

Action:
Edit the printer definition file and add the appropriate 'yes' or 'no'.

REP-01942
An error occurred in column {0} line {1} of file {2}: Expected name of character set to follow pcharset.

Category:
Other

Cause:
The printer definition file contains the 'pcharset' code string, but the required string (name of character set) is not specified.

Action:
Edit the printer definition file and add the name of character set.

REP-01943
An error occurred in column {0} line {1} of file {2}: Defined printer character set is unsupported.

Category:
Other

Cause:
The printer definition file contains an unsupported printer character set.

Action:
Edit the printer definition file and specify the name of a supported character set.

REP-01944
Invalid reference value {0} was specified for Report property {1}

Category:
Other

Cause:
The value specified for the indicated property cannot be resolved or is at a wrong frequency.

Action:
Ensure that the reference exists and resolves to a valid value. Only Report-level columns can be referenced with this property.

REP-01950
The Source specified is invalid.

Category:
Other

Cause:
The Source specified for Reports Converter is not a valid source.

Action:
Verify that the correct object or file is specified and that the STYPE is correct for that file or object.

REP-01951
The Destination specified is invalid.

Category:
Other

Cause:
The Destination specified for Reports Converter is not a valid destination.

Action:
Verify that the correct object or file is specified and that the DTYPE is correct for that file or object.

REP-01952
The number of Destination items must be zero or match the number of Source items.

Category:
Other

Cause:
In the Convert dialog box, or while using Reports Converter, the number of Destination items specified was greater than zero and did not match the number of Source items specified.

Action:
To have Oracle Reports Builder derive the Destination names from the specified Source names, leave Destination blank. Otherwise, verify that the number of Destination names specified matches the number of Source names specified. If wildcards are used in the Source specification, verify that the number of Destination names matches the number of Source items in the expanded wildcard list.

REP-02000
An error occurred in the user exit.

Category:
Other

Cause:
An error occurred in the user exit.

Action:
Debug the code or contact the database administrator.

REP-02001
An error occurred in IAF GET: unknown column {0}.

Category:
Other

Cause:
An unknown column name was specified in the user exit's IAF GET statement.

Action:
Specify a valid column name in the IAF GET statement.

REP-02002
An error occurred in IAF PUT: unknown column {0}.

Category:
Other

Cause:
An unknown column name was specified in the user exit's IAF PUT statement.

Action:
Specify a valid column name in the IAF PUT statement.

REP-02003
The user exit cannot be found.

Category:
Other

Cause:
Oracle Reports Builder could not find the user exit that it was supposed to run at this point. The most likely cause is that the name and/or location of the user exit code was not specified correctly.

Action:
Verify the name and location of the code when installing it. Otherwise, contact the database administrator.

REP-02004
PL/SQL source code of object {0} could not be retrieved.

Category:
Other

Cause:
From the File menu, Administration Report was selected to document one or more reports, but the RWEPLS user exit failed to retrieve the PL/SQL source code of an object. This is most likely an abnormal condition.

Action:
Check the PL/SQL source code in the named object. For assistance, contact Oracle Support Services.

REP-02005
An error occurred in IAF PUT: the value of column {0} was truncated.

Category:
Other

Cause:
The IAF PUT statement assigned a value to the named column, but the column was not wide enough to hold the entire value, causing it to truncate.

Action:
Widen the column so that it is can hold the entire value.

REP-02100
An error occurred in Calculation Manager.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-02101
Calculation Manager: the source column cannot use segmented memory.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-02102
Calculation Manager: the computed column cannot use segmented memory.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-02103
The PL/SQL formula returned invalid value or no value for column {0}.

Category:
Other

Cause:
An SRW.DO_SQL statement was entered that caused this Oracle message.

Action:
Edit the SRW.DO_SQL statement. For more information about the Oracle message, see the Oracle Messages and Codes Manual.

REP-02300
Error {0} occurred.

Category:
Other

Cause:
An SRW.DO_SQL statement was entered that caused this Oracle message.

Action:
Edit the SRW.DO_SQL statement. For more information about the Oracle message, see the Oracle Messages and Codes Manual.

REP-02301
An error occurred allocating a SQLDA descriptor: {0}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-02302
An error occurred parsing the SQL statement: {0}.

Category:
Other

Cause:
Oracle Reports Builder encountered an error while parsing the SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the SQL statement could not be parsed.

REP-02303
An error occurred describing bind variables: {0}.

Category:
Other

Cause:
Oracle Reports Builder encountered an error while describing bind variables in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the bind variables could not be described.

REP-02304
An error occurred opening a SQL cursor: {0}.

Category:
Other

Cause:
Oracle Reports Builder encountered an error while opening a cursor in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the cursor could not be opened.

REP-02305
An error occurred describing the SELECT list: {0}.

Category:
Other

Cause:
Oracle Reports Builder encountered an error while describing the SELECT list in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the bind variables could not be described.

REP-02306
An error occurred fetching bind variables: {0}.

Category:
Other

Cause:
Oracle Reports Builder encountered an error while fetching bind variables in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the bind variables could not be fetched.

REP-02307
An error occurred fetching a data record: {0}.

Category:
Data

Cause:
Oracle Reports Builder encountered an error while fetching a data record in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the data record could not be fetched.

REP-02308
An error occurred processing the SELECT list: {0}.

Category:
Other

Cause:
Oracle Reports Builder encountered an error while processing the SELECT list in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the SELECT list is invalid.

REP-02309
An error occurred formatting a date field: {0}.

Category:
Other

Cause:
Oracle Reports Builder encountered an error while formatting a date field in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the date field could not format.

REP-02310
An error occurred putting a value into a column: {0}.

Category:
Other

Cause:
Oracle Reports Builder encountered an error while trying to insert a value into a column in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the value could not be assigned.

REP-02311
An error occurred during Commit: {0}.

Category:
Other

Cause:
Oracle Reports Builder encountered an error while trying to do a commit in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the commit failed.

REP-02312
An error occurred allocating a data record: {0}.

Category:
Data

Cause:
Oracle Reports Builder encountered an error while allocating a data record in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the record could not be allocated.

REP-02313
An error occurred parsing the SELECT list: {0}.

Category:
Other

Cause:
Oracle Reports Builder encountered an error while parsing the SELECT list in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the SELECT list could not be parsed.

REP-02314
An error occurred closing a SQL cursor: {0}.

Category:
Other

Cause:
Oracle Reports Builder encountered an error while trying to close a SQL cursor in an SRW.DO_SQL statement.

Action:
Refer to the Oracle message to see why the close cursor operation failed.

REP-02315
An error occurred freeing a data record: {0}.

Category:
Data

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-02316
Column {0} cannot be found.

Category:
Other

Cause:
A column referred to in an SRW.DO_SQL statement cannot be found.

Action:
Debug the PL/SQL and verify that the SRW.DO_SQL statement contains the correct column name.

REP-02317
The value of column {0} was truncated.

Category:
Other

Cause:
A column value obtained via an SRW.DO_SQL statement was truncated.

Action:
Go to the column's Property Inspector and increase its Width. Or, restrict the size of the value that the SRW.DO_SQL statement is putting into the column.

REP-02400
DEBUG: internal error 0 occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-02500
Error {0} occurred. See the Release Notes for further information about this error

Category:
Other

Cause:
The error is documented in the Release Notes.

Action:
See the Release Notes.

REP-02550
The in-process server was not started: {0}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
Refer to the in-process server message to see why it failed to start. Then restart the Oracle Reports Builder.

REP-03000
An internal error occurred starting Oracle Toolkit.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03001
An internal error occurred initializing the File Dialog.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03002
An error occurred initializing the printer. Verify that a printer is installed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03020
An internal error occurred starting Oracle Resource Manager.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03021
An internal error occurred processing a menu resource.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03022
An internal error occurred processing a window resource.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03023
The resource file cannot be found.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03040
An internal error occurred starting Oracle Observer Model.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03060
An internal error occurred initializing the color table. Checking VGS resources is recommended.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03080
An internal error occurred initializing Oracle Image.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03081
An error occurred running the image viewer.

Category:
Other

Cause:
A Previewer button was selected with a defined action of displaying an image, but the image viewer is unavailable. Possible causes of this error include: Case 1: The image specified as

the source is in an incorrect format. Case 2: There is no available memory. Case 3: An abnormal condition was encountered.

Action:
Take the following actions to correct this error: If Case 1: Ensure that the image file specified as the source of the button action is in a displayable format. If Case 2: Make more memory available, if possible, or ask the system administrator for assistance. If Case 3: For assistance, contact Oracle Support Services.

REP-03082
An error occurred running the sound dialog.

Category:
Other

Cause:
A Previewer button was selected with a defined action of playing a sound, but the sound dialog is unavailable. Possible causes of this error include: Case 1: The sound file specified as the source is in an incorrect format. Case 2: There is no available memory. Case 3: An abnormal condition was encountered.

Action:
Take the following actions to correct this error: If Case 1: Ensure that the sound file specified as the source of the button action is in a playable format. If Case 2: Make more memory available, if possible, or ask the system administrator for assistance. If Case 3: For assistance, contact Oracle Support Services.

REP-03083
An error occurred running the video player.

Category:
Other

Cause:
A Previewer button was selected with a defined action of playing a video, but the video player is unavailable. Possible causes of this error include: Case 1: The video file specified as the source is in an incorrect format. Case 2: There is no available memory. Case 3: An abnormal condition was encountered.

Action:
Take the following actions to correct this error: If Case 1: Ensure that the video file specified as the source of the button action is in a playable format. If Case 2: Make more memory available, if possible, or ask the system administrator for assistance. If Case 3: For assistance, contact Oracle Support Services.

REP-03085
Multimedia source file {0} cannot be found.

Category:
Other

Cause:
The button was clicked in the Previewer, but the source for the button's intended action (whether sound, image, or video) cannot be found or has been corrupted.

Action:
Open the Property Inspector for the button in question and verify the existence, format, and path information for the specified source file.

REP-03086
The multimedia source file is not available.

Category:
Other

Cause:
The button was clicked in the Previewer, but the source for the button's intended action (whether sound, image, or video) has been corrupted.

Action:
Open the Property Inspector for the button in question and verify the existence, format, and path information for the specified source file. If it is correct, check the file itself.

REP-03087
ImageViewer is not supported in this configuration.

Category:
Other

Cause:
The platform or configuration does not support displaying images via the ImageViewer.

Action:
No action is necessary.

REP-03088
Sound is not supported in this configuration.

Category:
Other

Cause:
The platform or configuration does not support playback of sound files.

Action:
No action is necessary.

REP-03089
Video is not supported in this configuration.

Category:
Other

Cause:
The platform or configuration does not support playback of video files.

Action:
No action is necessary.

REP-03100
A matrix must include at least 1 Down and 1 Across repeating frame.

Category:
Other

Cause:
An attempt was made to create a matrix (selecting Arrange, then Create Matrix) without the proper objects selected in the Paper Layout editor. A matrix layout requires that at least one group have a repeat direction of Down and one have a repeat direction of Across.

Action:
Select two repeating frames--one Down, one Across--that overlap, then select Create Matrix from the Arrange Menu.

REP-03101
All selected Down and Across repeating frames must be nested.

Category:
Other

Cause:
An attempt was made to create a matrix (selecting Arrange, then Create Matrix) and the Down and Across repeating frames were not properly overlapping and nested.

Action:
Verify that the selected Down and Across repeating frames are properly overlapping and nested before creating the matrix.

REP-03102
Anchors, matrices, and margins cannot be grouped.

Category:
Other

Cause:
Group was selected from the Arrange menu and at least one of the objects selected was an anchor, matrix, or margin.

Action:
Deselect all anchors, matrices, and margins before grouping objects.

REP-03103
Only text and graphical boilerplate objects can be rotated.

Category:
Other

Cause:
An attempt was made to rotate a frame, a field, a margin, an anchor, a matrix object, a file link boilerplate object, or a graph. None of these can be rotated.

Action:
Rotate any boilerplate objects except images and file link boilerplate objects. Depending on the operating system, the text of a rotated boilerplate text object may or may not be visible.

REP-03104
Anchors and matrices cannot be scaled separately from their associated objects.

Category:
Other

Cause:
An attempt was made to scale one of the layout objects listed above without also scaling its associated object, which is not allowed.

Action:
Select at least one associated object (anchoring object for anchors, repeating frames for matrices), then retry the scaling operation.

REP-03105
A graph Column must be selected for the graph Query.

Category:
Other

Cause:
A name was entered for the graph Query, but no graph Columns were selected. If a graph Query is specified, graph Columns must also be specified.

Action:
Specify graph Columns or remove the value from the graph Query.

REP-03106
a graph Column was selected without a graph Query name. The selected graph Column will be ignored.

Category:
Other

Cause:
A Source or graph Column was selected but a name for a graph Query was not entered.

Action:
Enter the name of the graph query to which to pass data.

REP-03107
Object {0} cannot be moved in front of its child {1}.

Category:
Other

Cause:
An attempt was made to move a layout object in front of one or more of its own child objects.

Action:
To move the layout object, toggle Confine mode off, then move it. Otherwise, no action is necessary.

REP-03108
Object {0} cannot be moved behind its container {1}.

Category:
Other

Cause:
An attempt was made to move a layout object behind one or more of its own parent objects.

Action:
To move the layout object, toggle Confine mode off, then move it. Otherwise, no action is necessary.

REP-03109
The alignment operation failed because of container constraints.

Category:
Other

Cause:
An attempt was made to align multiple layout objects but the result of such an operation would have violated container constraints (that is, moved a field outside of its enclosing frame).

Action:
Select Edit, then Undo to ensure the layout is the same as before the attempted operation. Then, either resize or reposition the container in question to perform the operation, or do nothing.

REP-03110
Same size operation failed because of container constraints.

Category:
Other

Cause:
An attempt was made to change one or more layout objects to the same size, but the result of such an operation would have violated container constraints (that is, enlarged a field beyond its enclosing frame).

Action:
Select Edit, then Undo to ensure the layout is the same as before the attempted operation. Then, either resize or reposition the container in question to perform the operation, or do nothing.

REP-03111
Changing the border width of {0} violates the constraints of confined mode.

Category:
Other

Cause:
An attempt was made to change the border width of an object such that the result would have violated container constraints (that is, widening the border of a boilerplate object so that it extended beyond its enclosing frame).

Action:
No action is necessary.

REP-03112
Objects cannot be created in the template layout body layer.

Category:
Other

Cause:
An attempt was made to create an object in the layout body layer of a template. Objects may only be created in the margin, header pages, or trailer pages of a template.

Action:
No action is necessary.

REP-03130
Parameter Form fields and images cannot be rotated.

Category:
Other

Cause:
An attempt was made to rotate one of the Parameter Form objects, which is not allowed.

Action:
Rotate any boilerplate objects, except images, in the Parameter Form editor. Depending on the operating system, the text of boilerplate text that is rotated may or may not be visible.

REP-03131
Parameter Form boilerplate text cannot fit on the page.

Category:
Other

Cause:
Text was entered in the Title, Hint, Status, or Label field in the Parameter Form Builder that is too long to fit on the page.

Action:
Reduce the length of the appropriate text field.

REP-03140
A Program Unit Editor internal error occurred: Could not get document handle.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03150
One editor must remain open for each report.

Category:
Other

Cause:
An attempt was made to close all three of the editors (Data Model, Layout, and Parameter Form) for a report. At least one editor must remain open.

Action:
Leave one editor open for each report.

REP-03151
The width for column {0} is invalid and cannot be highlighted, since group {1} is not selected.

Category:
Other

Cause:
An invalid value was entered for the Width of a column in the Report Wizard. Since the group that owns the column is not selected, the column is not listed.

Action:
Select the group that owns the column. Scroll down to the column and enter a valid value for Width.

REP-03152
The link, anchor, or polygon creation must be completed in the editor before this action.

Category:
Other

Cause:
An attempt was made to perform some action (for example, close the report) before finishing the creation of a data link in the Data Model editor, an anchor in the Paper Layout editor, or a polygon in the Paper Layout editor or Parameter Form editor.

Action:
Complete the unfinished object before continuing.

REP-03153
Insufficient resources are available to create the window.

Category:
Other

Cause:
There were insufficient resources available to create the requested window.

Action:
Make more resources available by closing windows or other applications.

REP-03154
Insufficient resources are available to create the document.

Category:
Other

Cause:
There were insufficient resources available to create the requested document (report, external query, PL/SQL library).

Action:
Make more resources available by closing windows or other applications.

REP-03200
Concurrent previewer actions are not allowed.

Category:
Other

Cause:
An attempt was made to activate more than one button at one time, in either the same or multiple Previewers. For example, play a sound and display a video at the same time.

Action:
Activate only one button at a time.

REP-03290
Query Builder does not support lexical parameters.

Category:
Other

Cause:
An attempt was made to pass lexical parameters to Query Builder, which is not supported. Query Builder only supports bind parameters.

Action:
Remove all lexical parameters from the query and reenter Query Builder.

REP-03300
A fatal error occurred: {0}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03301
An error occurred: {0}.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03302
A fatal error occurred during Quit. Exiting Oracle Reports Builder.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03335
An unhandled internal CA error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03350
An unhandled internal UI error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03351
An undefined failure in the UI occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03352
An unexpected error in the UI occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03353
The attribute cannot be created.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03354
The attribute cannot be set.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03355
The attribute cannot be set or retrieved.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03356
The unknown attribute cannot be set or retrieved.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03357
The attributes values are conflicting and cannot be set.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03358
The attribute cannot be set to an out of range value.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03359
This function call is out of context.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03360
The view class does not support being a scrollee.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03361
This function call provokes an illegal recursion.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03362
The internal API memory allocator failed.

Category:
Memory

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03363
The client supplied memory allocation functions failed.

Category:
Memory

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03364
An attempt to use an unsupported function failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03365
Attributes cannot be set out of context.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03366
An attempt to perform an illegal operation on a root view failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03367
One of the parameters to the functions is out of range.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03368
The connection to the windowing system failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03369
The connection to the windowing system is broken.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03370
The windowing system failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03371
uiER_CL_FORMAT_UNAVAILABLE

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03372
uiER_CL_FORMAT_UNREGISTERED

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03373
The operation timed out.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03374
uiER_NOT_FOUND

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03375
uiER_ILLEGAL_TOPITEM

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03376
uiER_SE_BAD_FORMAT

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03377
The view class does not support the scroller interface.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03378
An attempt to remove a readshare color from a palette failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03379
An attempt to create a window failed.

Category:
Other

Cause:
Oracle Reports Builder was unable to create a window. There may be too many reports or windows open, and lack of memory resources.

Action:
Close some reports and windows.

REP-03380
An attempt to create a view failed.

Category:
Other

Cause:
Oracle Reports Builder was unable to create a view. There may be too many reports or windows open, and lack of memory resources.

Action:
Close some reports and windows.

REP-03381
An attempt to create a color palette failed.

Category:
Other

Cause:
Oracle Reports Builder was unable to create a color palette. There may be too many reports or windows open, and lack of memory resources.

Action:
Close some reports and windows.

REP-03400
An error occurred initializing DE. Checking DE resources is recommended.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03420
An internal error occurred in Oracle Reports Builder.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03430
An unhandled internal HH error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03431
The attribute value is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03432
The context is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03433
The specified word cannot be found.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03434
A link to external document was found.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03435
The help session is null.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03436
The document is not a help document.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03437
The document revision is newer than help.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03438
The specified attribute is not settable.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03439
The specified attribute is not gettable.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03440
The link is invalid.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03441
Logical attributes are missing or bad.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03442
The NLS language string is missing or bad.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03443
No search string is specified.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03444
The string begins with a percent sign.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03445
An unknown toolkit error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03446
An unknown object store error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03447
An out of memory condition occurred.

Category:
Memory

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03448
An unknown Resource Manager error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03480
An unhandled internal REM error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03485
An unhandled internal VGS error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03500
An unhandled internal UT error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03510
An unhandled internal ZOM error occurred.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03600
Both document nodes and non-document nodes selected. Select only nodes from one of these types of nodes.

Category:
Other

Cause:
Navigator>Delete was selected, but both object nodes and document nodes are selected. Documents cannot be closed and deleted in the same action.

Action:
To delete objects, deselect all document nodes. To close documents, deselect all object nodes. Then select Navigator>Delete again.

REP-03601
This report style can only have one Section.

Category:
Other

Cause:
Tabular, Form Letter, and Mailing Label report styles have only one Section each.

Action:
Specify all overrides in the existing Section.

REP-03602
The minimum number of levels cannot be deleted.

Category:
Other

Cause:
Tabular, Form Letter, and Mailing Label report styles have one Section each. Group Above and Group Left report styles have two sections each. Matrix and Matrix Group have one section under each normal, across, and down cell.

Action:
Verify that the particular report style has the minimum number of levels.

REP-03700
Selection Observer initialization failed.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-03701
Selection Observer failed while shutting down.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-04001
An error occurred in the OLE subsystem.

Category:
Other

Cause:
An unspecified OLE2 error occurred during initialization. Refer to the accompanying OLE error message for more information. Other possible causes of this error include the following: Case 1: The OLE2 server is not functioning correctly. Case 2: An error occurred during installation of Oracle Reports Builder and the OLE2 functionality did not install correctly. Case 3: An abnormal condition was encountered.

Action:
Take the following actions to correct this error: If Case 1: Refer to the OLE2 server documentation for more information. If Case 2: Reinstall Oracle Reports Builder. If Case 3: For assistance, contact Oracle Support Services.

REP-04002
An error occurred while initializing OLE subsystem.

Category:
Other

Cause:
An error occurred during initialization of OLE2 libraries. Refer to the accompanying OLE error message for more information. Other possible causes of this error include the following: Case 1: The OLE2 server is not functioning correctly. Case 2: An error occurred during installation of Oracle Reports Builder and the OLE2 functionality did not install correctly. Case 3: An abnormal condition was encountered.

Action:
Take the following actions to correct this error: If Case 1: Refer to the OLE2 server documentation for more information. If Case 2: Reinstall Oracle Reports Builder. If Case 3: For assistance, contact Oracle Support Services.

REP-04003
An error occurred while creating OLE object.

Category:
Other

Cause:
An attempt was made to create an OLE2 object when an OLE error occurred.

Action:
Refer to the accompanying OLE2 error message for more information.

REP-04004
An error occurred while restoring OLE object.

Category:
Other

Cause:
An attempt was made to restore an OLE2 object when an OLE error occurred.

Action:
Refer to the accompanying OLE2 error message for more information.

REP-04005
An error occurred while saving OLE object.

Category:
Other

Cause:
An attempt was made to save an OLE2 object when an OLE error occurred.

Action:
Refer to the accompanying OLE2 error message for more information.

REP-04006
An error occurred while performing a cut/copy operation. An OLE object is not placed in the clipboard.

Category:
Other

Cause:
An attempt was made to cut or copy an OLE2 object when an OLE error occurred.

Action:
Refer to the accompanying OLE2 error message for more information.

REP-04007
An error occurred while pasting OLE object from clipboard.

Category:
Other

Cause:
An attempt was made to paste an OLE2 object from the clipboard when an OLE error occurred.

Action:
Refer to the accompanying OLE2 error message for more information.

REP-04008
An error occurred while trying to perform operation defined by an OLE object.

Category:
Other

Cause:
An attempt was made to perform an action normally supported by the OLE2 server when an OLE error occurred.

Action:
Refer to the accompanying OLE error message for more information.

REP-04009
An error occurred while trying to activate an OLE object.

Category:
Other

Cause:
An attempt was made to activate an OLE2 object (for example, double-click on it in the Previewer) when an OLE error occurred.

Action:
Refer to the accompanying OLE2 error message for more information.

REP-04020
Conversion of OLE object to a different type failed.

Category:
Other

Cause:
An attempt was made to convert an OLE2 object contained in a piece of boilerplate to an OLE2 object of a different type when an OLE error occurred. This indicates a problem with the OLE2 server.

Action:
Check that the object is correctly installed and reinstall, if necessary.

REP-04021
Microsoft Object Linking and Embedding is not supported on this platform

Category:
Other

Cause:
An attempt was made to run a report that was created on a platform supporting OLE2, and created with OLE2 objects, on a platform that does not support OLE2.

Action:
No action is necessary. Remove the object if desired.

REP-04022
The incorrect version of OLE libraries are installed. OLE functionality will be disabled.

Category:
Other

Cause:
The OLE2 libraries installed are incompatible with those supported by the installed version of Oracle Reports Builder. As Oracle Reports Builder cannot guarantee that the OLE2 support will function, it disabled OLE2 functionality.

Action:
Install the correct libraries.

REP-04023
There is insufficient memory available to complete the operation.

Category:
Memory

Cause:
There is not sufficient memory remaining on the system to perform the desired action.

Action:
Exit any unnecessary applications that are running. If that does not work, see the Microsoft documentation for suggested procedures to enhance memory usage.

REP-04024
DOS SHARE services are required for successful operation. SHARE is not running.

Category:
Other

Cause:
The DOS SHARE utility is required, but SHARE is not running.

Action:
Verify that SHARE is running.

REP-04025
A read failure occurred.

Category:
Other

Cause:
Data cannot be read from the specified device.

Action:
Check the device to determine if it is malfunctioning, and, if so, consult the device documentation to determine the proper error recovery procedures.

REP-04026
A write failure occurred.

Category:
Other

Cause:
Data cannot be written to the specified device.

Action:
Check the device to determine if it is read-only. If not, consult the device documentation to determine the proper error recovery procedures.

REP-04027
Too many files opened. There are insufficient resources to open another file.

Category:
Other

Cause:
An attempt was made to open more files than are supported by Windows.

Action:
Close some applications. Also, check the config.sys file and ensure that FILES is not set below 20. Note: Remember that OLE2 boilerplate objects reserve either two or three file handles per object and so there may be more files open than expected.

REP-04028
No space is left on the device.

Category:
Other

Cause:
The device is full.

Action:
Delete unnecessary data or write to a different device.

REP-04029
Presentation of the OLE object failed. Cannot render OLE object.

Category:
Other

Cause:
An attempt was made to display an OLE2 object in a report but the display aspects defined by the OLE2 server were unavailable.

Action:
Verify that the OLE2 object has not been corrupted and that the server is correctly installed. Reinstall if necessary.

REP-04030
Restoration of original display aspects of the OLE object failed. Object content will be used.

Category:
Other

Cause:
An attempt was made to display an OLE2 object in a report but the display aspects defined by the OLE2 server were corrupted or stored in the database and could not be restored. Oracle Reports Builder will display the object using the default aspect.

Action:
Verify that the OLE2 server is correctly installed. Reinstall if necessary.

REP-04031
The server application cannot be found.

Category:
Other

Cause:
An attempt was made to access an OLE2 server via an OLE2 object, but the server is currently inaccessible. The server may have been deleted, renamed, or manually reinstalled in a different location.

Action:
Check the installation of the server and reinstall if necessary.

REP-04032
Connection to the linked OLE object source failed.

Category:
Other

Cause:
Oracle Reports Builder is trying to connect to the specified source of the OLE2 object boilerplate but cannot.

Action:
Verify that the OLE2 object source has not been moved or deleted, and that its file name has not been changed.

REP-04033
Connection to the linked object source failed, because it is across a network that is not connected to this machine.

Category:
Network

Cause:
An attempt was made to link to an OLE2 object that is stored on a device to which there is no established network connection.

Action:
Establish a connection to the proper device.

REP-04034
A file cannot be not found or an invalid file name is used by an OLE object.

Category:
Other

Cause:
An OLE2 object is attempting to access a file that it cannot find.

Action:
Verify that the file has not been corrupted, moved, or renamed.

REP-04035
A share violation has occurred while performing operation on OLE object.

Category:
Other

Cause:
Possible causes: an attempt was made to link to the same file via multiple OLE2 objects, or to access the same temporary file via different applications.

Action:
Verify multiple OLE2 objects are not attempting to access the same file at the same time. Also, check the intallation of the OLE2 server.

REP-04036
Access was denied while performing an operation on an OLE object.

Category:
Other

Cause:
An attempt was made to update an OLE2 object without write access.

Action:
Obtain the proper permissions to the file before trying to update it.

REP-04037
File operation on OLE object failed because disk is write-protected.

Category:
Other

Cause:
An attempt was made to save to file an OLE2 object but it failed because the disk is write-protected.

Action:
Save the object to a disk with write privileges, if possible. If not, no action is necessary.

REP-04038
Unexpected error occurred in the file system while performing an operation on an OLE object.

Category:
Other

Cause:
A non-specific file error such as a corruption of the hard disk occurred.

Action:
Refer to the operating system documentation more information.

REP-04039
An unexpected error was returned by OLE.

Category:
Other

Cause:
A non-specific OLE error occurred.

Action:
Refer to the Microsoft documentation for more information.

REP-04040
Incorrect or corrupted OLE object persistent data was encountered. The OLE object cannot be restored from this data

Category:
Data

Cause:
The information used by the OLE server to restore the OLE2 object in the report is incorrect or has been corrupted. Possible causes for this error include: Case 1: If boilerplate, the file has become corrupted. Case 2: If field, either the database has been corrupted, or the LONG RAW column referenced does not contain OLE2 objects.

Action:
Take the following actions to correct this error: If Case 1: Verify that the object is viable by embedding it in a container using another application. If Case 2: Use SQL*Plus to check the table in the database and verify the contents of the column.

REP-04041
No operations are defined on this object or the object is static.

Category:
Other

Cause:
An attempt was made to take some action on an OLE2 object but no actions have been defined as applying to the object. Possibly the object was converted to a static bitmap.

Action:
No action is necessary.

REP-04042
The requested action on the OLE object is valid, but cannot be performed at this moment. The object server may be busy.

Category:
Other

Cause:
An attempt to take a valid action on an OLE2 object failed, due to lack of server resources. A possible cause is that an attempt was made to open a second instance of a single-instance application.

Action:
Check system resources (such as memory) and increase where possible, or try the operation later.

REP-04043
The operation requested on the object is invalid and cannot be performed.

Category:
Other

Cause:
The action attempted on an OLE2 object was not recognized as valid.

Action:
Verify that the proper version of the OLE server is correctly installed. Reinstall if necessary.

REP-04044
The system registry cannot be accessed.

Category:
Other

Cause:
A read or write operation in the system registry failed.

Action:
Verify that there are enough free system resources and the registry is not corrupted. Consult the Microsoft documentation.

REP-04045
A problem occurred in the system registry.

Category:
Other

Cause:
Some information about the server is missing from the registry.

Action:
Verify that the OLE server is installed correctly. Reinstall if necessary.

REP-04100
An attempt to execute data source failed.

Category:
Data

Cause:
An internal error occurred while executing the specific pluggable data source.

Action:
Look for more details in the engine trace.

REP-04101
An attempt to create conditions for pluggable data source failed.

Category:
Data

Cause:
An internal error occurred while creating conditions for the specific pluggable data source.

Action:
Look for more details in the engine trace in case of a custom PDS.

REP-04102
An attempt to fetch pluggable data source failed.

Category:
Data

Cause:
An internal error occurred when fetching the resultset of the pluggable data source.

Action:
Look for more details in the engine trace in case of a custom PDS.

REP-04103
An attempt to set up pluggable data source driver failed.

Category:
Data

Cause:
An internal error occurred.

Action:
Verify the installation. For assistance, contact Oracle Support Services.

REP-04104
Pluggable data source {0} references unknown column {1}

Category:
Data

Cause:
An invalid column is being referenced in the pluggable data source query.

Action:
Verify the PDS query.

REP-04105
An attempt to create pluggable data source factory {0} failed.

Category:
Data

Cause:
The pluggable data source factory class specification in the preference file is invalid.

Action:
Validate the specification of pluggable data source factory classes in the preference file.

REP-04106
An attempt to edit the query failied because it was created with a later version ({0}) of pluggable data source factory {1}.

Category:
Data

Cause:
Query was created with a later version of pluggable data source factory than the current Builder session's registered factory. For this to occur, the major version of the factories must be different. Major version is the value left of the decimal point in the factory version number.

Action:
Upgrade the registered Oracle Reports Builder pluggable data source factory to one with the equivalent major version number.

REP-04107
The query will be upgraded from version {0} to current factory version {1}.

Category:
Other

Cause:
The query was created with an earlier version of pluggable data source factory than the current Builder session's registered factory. For this to occur, the major version of the factories must be different. Major version is the value left of the decimal point in the factory version number.

Action:
No action is necessary. The query will be automatically upgraded to the version number of the current factory.

REP-04108
The version of the query {0} is different from the pluggable data source factory {1}.

Category:
Data

Cause:
The query was created with version of pluggable data source factory that is slightly different than the current Builder session's registered factory. For this to occur, the minor version of the factories must be different. Minor version is the value right of the decimal point in the factory version number.

Action:
No action is necessary. The Edit operation will proceed.

REP-04109
Factory {0} is not a registered factory class.

Category:
Other

Cause:
The factory class may not be specified correctly in the preference file.

Action:
Verify that the factory class is specified correctly in the preference file.

REP-04110
Query definition for query {0} cannot be found.

Category:
Other

Cause:
Oracle Reports Builder could not connect to the data source referred in the query.

Action:
Check the connection information for the PDS query.

REP-04111
Pluggable data source {0} cannot be created.

Category:
Data

Cause:
Case 1: There is no JVM. Case 2: There is no Oracle Reports pluggable data source driver. Case 3: Pluggable data source class failed to return new pluggable data source object.

Action:
In Case 1: Check the Oracle Reports and Java installation on the machine. In Case 2: Check if the correct Oracle Reports jar file is in the right place. In Case 3: Check if the right pluggable data source class is in place.

REP-04112
Oracle Reports Builder can not display the image for pluggable data source {0}.

Category:
Data

Cause:
The bitmap image may be corrupted.

Action:
Verify that the bitmap image is not corrupted by confirming that it is saved in .gif format and it can be viewed in the appropriate image tool.

REP-04113
Changing the type of pluggable data source bound to this parameter may affect query behavior in the Data Model.

Category:
Data

Cause:
An attempt was made to change a query of one PDS type to another.

Action:
Verify any parameters used in the query when changing PDS type.

REP-04200
An error occurred in the Mail subsystem.

Category:
Other

Cause:
An unspecified error occurred during one of the mail operations. Refer to the accompanying error message for more information. Other possible causes of this error include the following: Case 1: MAPI is not properly installed. Case 2: The Windows mail service provider is not properly installed.

Action:
Take the following actions to correct this error: If Case 1: For other applications using MAPI, check to see if they are functioning properly. If not, try reinstalling MAPI. If Case 2: Verify that the Windows mail service provider is installed, and a mail account exists on the system. For assistance, ask the mail administrator.

REP-04201
An error occurred while initializing the Mail subsystem.

Category:
Other

Cause:
Oracle Reports Builder tried to initialize MAPI, and could not. Refer to the accompanying error message for more information. Other possible causes of this error include the following: Case 1: MAPI is not installed, the MAPI DLL is out of date, or the Mail entry in the WIN.INI file or registry points to the wrong location. Case 2: There is not enough memory available to perform the operation. Case 3: While logging on, an invalid service profile name, username, or password was entered.

Action:
Take the following actions to correct this error: If Case 1: Reinstall MAPI, or correct the Mail entry in the WIN.INI file or registry. If Case 2: Exit any unnecessary applications that are running. If that does not work, see the Microsoft documentation for suggested procedures to enhance memory usage. If Case 3: Verify that the logon information is correct, and try again. If that does not work, confirm the account information with the mail administrator.

REP-04202
An error occurred while logging on to the Mail subsystem.

Category:
Logging

Cause:
An attempt was made to log on to the Mail subsystem and an error occurred. Refer to the accompanying error message for more information. Other possible causes of this error include the following: Case 1: An invalid service profile name, username, or password was entered. Case 2: There is not enough memory available.

Action:
Take the following actions to correct this error: If Case 1: Verify that the logon information is correct, and try again. If that does not work, confirm the account information with the mail administrator. If Case 2: Exit any unnecessary applications that are running. If that does not work, see the Microsoft documentation for suggested procedures to enhance memory usage.

REP-04203
An error occurred while sending a mail message.

Category:
Other

Cause:
An error occurred while composing or sending a mail message. Refer to the accompanying error message for more information. Other possible causes of this error include the following: Case 1: There is not enough free space on the disk. Case 2: There is not enough memory available.

Action:
Take the following actions to correct this error: If Case 1: Free up some space on the disk. If Case 2: Exit any unnecessary applications that are running. If that does not work, see the Microsoft documentation for suggested procedures to enhance memory usage.

REP-04204
An error occurred while trying to validate recipient's name or address.

Category:
Other

Cause:
Oracle Reports Builder tried to validate the destination mail address, and an error occurred.

Action:
Confirm that the recipient has a valid mail account, or ask the mail administrator for assistance. Refer to the accompanying error message for more information.

REP-04220
There is a problem with the Mail subsystem.

Category:
Other

Cause:
An unspecified error occurred during one of the mail operations.

Action:
Try to free up some disk space or exit any unnecessary applications that are running. If other applications are using MAPI, check to see if they are functioning properly. If not, try reinstalling MAPI.

REP-04221
An attachment file cannot be accessed.

Category:
Other

Cause:
An error occurred while trying to access attachment file. Possible causes of this error include the following: Case 1: The attachment file cannot be found. Case 2: The attachment file could not be opened, or there was an error reading or writing it.

Action:
Take the following actions to correct this error: If Case 1: Exit any unnecessary applications that are running. If that does not work, see the Microsoft documentation for suggested procedures to enhance memory usage. If Case 2: Free up some space on the disk.

REP-04222
There is insufficient memory to complete the operation.

Category:
Memory

Cause:
The mail operation cannot be completed, because there is not enough memory available.

Action:
Exit any unnecessary applications that are running. If that does not work, see the Microsoft documentation for suggested procedures to enhance memory usage.

REP-04223
No space is left on the device.

Category:
Other

Cause:
The mail operation cannot be completed because there is not enough free space available on the disk.

Action:
Free up some space on the disk.

REP-04224
The user name, password, or service profile name is incorrect.

Category:
Other

Cause:
The logon information entered is invalid.

Action:
Verify that the logon information is correct, and try again. If that does not work, confirm the account information with the mail administrator.

REP-04225
The operation cannot be completed because the user is not logged on.

Category:
Other

Cause:
The mail operation could not be completed.

Action:
Log on to the Mail subsystem, and try again.

REP-04226
A password is required.

Category:
Other

Cause:
An attempt was made to log on to the Mail subsystem without specifying a password.

Action:
Specify a valid password, and try again. If that does not work, contact the mail administrator.

REP-04227
The service configuration is invalid.

Category:
Configuration

Cause:
The Mail subsystem is incorrectly configured.

Action:
Contact the mail administrator.

REP-04228
MAPI does not support the service requested by Oracle Reports Builder.

Category:
Other

Cause:
The given implementation of MAPI has limited functionality.

Action:
Consider upgrading the Windows mail service provider. Contact the mail administrator.

REP-04229
The character set requested is not supported.

Category:
Other

Cause:
The default character set is not supported by MAPI.

Action:
Contact the mail administrator.

REP-04230
The size of the text string passed is too large.

Category:
Other

Cause:
The text string passed is too large for the given implementation of MAPI.

Action:
Shorten the string, and try again.

REP-04232
Too many files are opened.

Category:
Other

Cause:
The given implementation of MAPI does not support the number of files open.

Action:
Close all unnecessary documents.

REP-06004
Oracle Reports Builder failed to connect to the specified Express server.

Category:
Other

Cause:
Express server is not running.

Action:
Verify that Express server is running.

REP-06006
The Express initialization file, XPDATA.INI, cannot be found.

Category:
Other

Cause:
The Express initialization file, XPDATA.INI, was not found.

Action:
Check the existence and path of the XPDATA.INI file.

REP-06007
The Express connection file (XCF) entry cannot be found in the [Install] section of the Express initialization file, XPDATA.INI.

Category:
Other

Cause:
The Express connection file (XCF) entry was not found in the [Install] section of the Express initialization file, XPDATA.INI.

Action:
Add an XCF entry to XPDATA.INI file, or replace with a valid XPDATA.INI.

REP-06008
The path specified in ORACLE_HOME cannot be found.

Category:
Other

Cause:
The path specified in the the ORACLE_HOME variable was not found.

Action:
Check the ORACLE_HOME setting.

REP-06009
The Oracle SNAPI (OSN) entry cannot be found in the [Install] section of the Express initialization file, XPDATA.INI.

Category:
Other

Cause:
The Oracle SNAPI (OSN) entry was not found in the [Install] section of the Express initialization file, XPDATA.INI.

Action:
Add an OSN entry to XPDATA.INI, or replace with a valid XPDATA.INI.

REP-06010
The Express server description cannot be found in any Express connection files (XCFs).

Category:
Other

Cause:
The Express server description was not found in any Express connection files (XCFs).

Action:
Check the XCF files.

REP-06011
The size of the generated SQL SELECT statement exceeds the 64K limit.

Category:
Other

Cause:
The size of the generated SQL SELECT statement exceeds the 64K limit.

Action:
Modify the query to reduce the size of the SQL statement.

REP-06013
A query failed to run. The Express Query Dialog was invoked with a set of measures/dimensions from a previous query

Category:
Other

Cause:
The Express Query Dialog was invoked with a set of measures/dimensions from a previous query.

Action:
Reexamine the measures/dimensions in the query.

REP-06014
The report ID was not defined when calling the backend XPFetch[N().

Category:
Other

Cause:
The report ID was not defined before calling the backend XPFetch().

Action:
Define the report ID and resubmit the call to the backend XPFetch().

REP-06015
A duplicate report ID was used when calling the backend XPPrepare().

Category:
Other

Cause:
A duplicate report ID was used when the backend XPPrepare() was called.

Action:
Select a unique report ID and resubmit the call to the backend XPPrepare().

REP-06017
The saved query contained incorrect or missing information.

Category:
Other

Cause:
When the query was saved, it contained incorrect or missing information.

Action:
Check the query and correct the information or supply the missing information and try again.

REP-06018
The internal Oracle Express system databases were not attached.

Category:
Other

Cause:
The internal Oracle Express system databases were not attached.

Action:
Attach the internal Oracle Express system databases and try again.

REP-06019
The Oracle Express database specified in the saved query was not attached.

Category:
Other

Cause:
The Oracle Express database that was specified in the saved query was not attached.

Action:
Attach the specified Oracle Express database to the saved query and try again.

REP-06021
The Oracle Express support was not installed.

Category:
Other

Cause:
The Oracle Express support was not installed.

Action:
Install the Oracle Express support and try again.

REP-06023
An unexpected end-of-line was received while parsing the Oracle Express query.

Category:
Other

Cause:
The Oracle Express query might be missing the \s at the end of the line.

Action:
Check the Oracle Express query for a missing \s at the end of the line, add it, and try again.

REP-06026
A duplicate report ID was detected.

Category:
Other

Cause:
A duplicate report ID was used.

Action:
Select a unique report ID and try again.

REP-06027
An undefined report ID was detected.

Category:
Other

Cause:
The report ID that was used has not yet been defined.

Action:
Define the report ID and try again.

REP-06030
The XCONNECT.INI file was missing or was invalid.

Category:
Other

Cause:
This message probably occurred as the result of a missing XCONNECT.INI file. If the XCONNECT.INI file is not missing, then it probably has an invalid General section.

Action:
Check in ORACLE_HOME/OLAP/ECF620 to ensure that the XCONNECT.INI file is there. If not, then add it. If the XCONNECT.INI file is there, verify that it has a valid General section.

REP-06031
This report contains Oracle Express queries that are 6i versions. Convert these queries?

Category:
Other

Cause:
An older version of Oracle Express queries cannot be edited or run with the current version of Oracle Express.

Action:
Reply YES to converting the older version of Oracle Express queries to the newer version of Oracle Express. The queries will be automatically converted.

REP-06032
The Oracle Express query {0} failed to convert.

Category:
Other

Cause:
This error message could have occurred for one of the following reasons: Case 1: The Oracle Express 6i query was corrupted. Case 2: The Oracle Express pluggable data source malfunctioned.

Action:
Take the following actions to correct this error: If Case 1: Ensure that the query is not corrupted by editing and rerunning it in the OracleAS Reports Services environment. If Case 2: For assistance, contact Oracle Support Services.

REP-06033
This operation requires converting the {0} Oracle Express query to the newer version of Oracle Express. Proceed with this conversion?

Category:
Other

Cause:
Older versions of Oracle Express queries cannot be edited or run with the current version of Oracle Express.

Action:
Accept the conversion by replying YES to the conversion. The queries will be automatically converted.

REP-06051
The Oracle Portal connection failed.

Category:
Other

Cause:
The database server might be down or the user ID and password authentication failed.

Action:
Check that the database server is available, verify that the user ID and password are correct and try again.

REP-06052
The database requested does not contain a valid Oracle Portal definition.

Category:
Other

Cause:
This error might have occurred for one of the following reasons: Case 1: The database is not a valid version for the Oracle Portal installation. Case 2: The logged in user does not have permission to read the component definition tables.

Action:
Take the following actions to correct this error: If Case 1: Select a valid database for the Oracle Portal installation. If Case 2: Obtain permissions for the logged in user to read the component definition tables.

REP-06053
There are no components in Oracle Portal that can be imported.

Category:
Other

Cause:
This is an information only message notifying that there are no components available to be imported.

Action:
No action is necessary.

REP-06054
The requested template cannot be found.

Category:
Other

Cause:
This can occur for one of the following reasons: Case 1: The REPORTS_XSL_TEMPLATE environment variable was incorrectly edited. Case 2: The template XSL file was removed from the location where it is supposed to be located.

Action:
Take the following actions to correct this error: If Case 1: Correct the REPORTS_XSL_TEMPLATE and continue. If Case 2: Ensure the template XSL file is in the proper location and continue.

REP-06055
A template error occurred.

Category:
Other

Cause:
The XSL template file was not a well-formed template.

Action:
Verify that the XSL template file is correct. If it is, then the best solution is to restore the original one. Experienced users can edit the file to correct the problems.

REP-06056
A temporary directory was invalid.

Category:
Other

Cause:
The transformation process requires a temporary directory to write a temporary file. The temporary directory might not exist or it might not allow a temporary file to be written to it.

Action:
Look at the REPORTS_TMP environment variable and ensure that it corresponds to an existing, writable temporary directory.

REP-06057
A portal component has not been selected.

Category:
Other

Cause:
OK was clicked without selecting a portal component.

Action:
Select a portal componet or click Cancel.

REP-06058
Database client library error.

Category:
Other

Cause:
Oracle Reports cannot connect to the portal database because of a JDBC error. A common cause is a version mismatch of a database client library in the path.

Action:
Verify that the Oracle Reports bin directory is listed in the path search order before any other ORACLE_HOME/bin or other directory that could have a database client. If this does not solve the problem, check the Java classpath and verify that the correct version of the JDBC library is listed before any other library.

REP-06101
The Java Virtual Machine failed to start. Check the Java Runtime Environment setup. {0}:{1}.

Category:
Other

Cause:
The Java runtime environment in the installation is not valid.

Action:
Verify that the installation is correct. Reinstall if necessary.

REP-06102
The XML parser failed to start.

Category:
Other

Cause:
The XML parser jar files are missing in the installation.

Action:
Verify that the Oracle Fusion Middleware installation is correct. Reinstall if necessary.

REP-06103
An error occurred with the Java Runtime Environment setup.

Category:
Other

Cause:
The Java runtime environment in the installation is not valid.

Action:
Verify that the installation is correct. Reinstall if necessary.

REP-06104
The XML report definition is invalid.

Category:
Other

Cause:
The report definition is invalid.

Action:
Verify the XML report definition.

REP-06105
An error occurred in the XML report definition at line {0}.

Category:
Other

Cause:
The report definition is invalid.

Action:
Verify the XML report definition.

REP-06106
An error occurred in the XML report definition at line {0} in {1}.

Category:
Other

Cause:
The report definition is invalid.

Action:
Verify the XML report definition.

REP-06107
The URL for the XML report definition is invalid: {0}.

Category:
Other

Cause:
The report definition is invalid.

Action:
Verify the URL location / XML report definition.

REP-06108
The XML report definition cannot be applied.

Category:
Other

Cause:
This is an internal error.

Action:
For assistance, contact Oracle Support Services.

REP-06109
The report definition file {0} cannot be saved.

Category:
Other

Cause:
This is an internal error.

Action:
For assistance, contact Oracle Support Services.

REP-06110
The query {0} cannot be created.

Category:
Other

Cause:
The PDS query is invalid.

Action:
Look into the trace information for more details in case of a custom PDS.

REP-06111
The query {0} cannot be modified.

Category:
Other

Cause:
The PDS query is invalid.

Action:
Look into the trace information for more details in case of a custom PDS.

REP-06112
The column {0} cannot be created.

Category:
Other

Cause:
The PDS query is invalid.

Action:
Look into the trace information for more details in case of a custom PDS.

REP-06113
The column {0} cannot be modified.

Category:
Other

Cause:
The PDS query is invalid.

Action:
Look into the trace information for more details in case of a custom PDS.

REP-06114
The data link {0} cannot be created.

Category:
Data

Cause:
The PDS query is invalid.

Action:
Look into the trace information for more details in case of a custom PDS.

REP-06115
The data link {0}cannot be modified.

Category:
Data

Cause:
The PDS query is invalid.

Action:
Look into the trace information for more details in case of a custom PDS.

REP-06116
The field {0} cannot be created.

Category:
Other

Cause:
The PDS query is invalid.

Action:
Look into the trace information for more details in case of a custom PDS.

REP-06117
The field {0} cannot be modified.

Category:
Other

Cause:
The PDS query is invalid.

Action:
Look into the trace information for more details in case of a custom PDS.

REP-06118
The layout for {0} cannot be defaulted.

Category:
Other

Cause:
This is an internal error.

Action:
Contact Oracle Support Services if the problem persists.

REP-06119
Format exception {0} for the field {1} cannot be created.

Category:
Other

Cause:
This is an internal error.

Action:
Contact Oracle Support Services if the problem persists.

REP-06120
Condition {0} in the format exception {1} for the field {2} is invalid.

Category:
Other

Cause:
This is an internal error.

Action:
Contact Oracle Support Services if the problem persists.

REP-06121
The specified layout style {0} is invalid.

Category:
Other

Cause:
An attempt was made to use an invalid layout style.

Action:
Verify the layout style for the report.

REP-06122
The specified layout style {0} in {1} is invalid.

Category:
Other

Cause:
An attempt was made to use invalid layout style.

Action:
Verify the layout style for the report.

REP-06123
Source {0} for field {1} is invalid.

Category:
Other

Cause:
The value used for the field is invalid.

Action:
Verify the value.

REP-06124
A PL/SQL compilation error occurred in {0}.

Category:
Other

Cause:
The PL/SQL procedure is invalid.

Action:
Verify the PL/SQL procedure.

REP-06200
Reports tag library directive cannot be found: {0} in report file

Category:
Other

Cause:
Reports was unable to locate the expected JSP taglib directive in the user supplied report file.

Action:
All Web-based reports must contain the tag library directive. Open any demo .JSP file and copy the taglib lines into the report.

REP-06201
Prefix attribute {0} in report file cannot be found.

Category:
Other

Cause:
The file does not contain an rw:objects tag. The tag library directive does not contain the correct prefix attribute or is otherwise corrupted.

Action:
The rw:objects tag supplies data for report blocks and charts. If this tag is not required in the file then this message can be ignored. If data is required, use the data wizard to add a data model to the report. Open any demo .jsp file and replace the taglib lines in the report with the lines from the demo file.

REP-06202
A rw:report tag in the template file cannot be found.

Category:
Other

Cause:
The file contains a taglib directive but does not contain a rw:report tag.

Action:
The template file can still be used but the rw:report tag must be added to a report before a data model can be added.

REP-06203
Template file cannot be parsed.

Category:
Other

Cause:
Reports was unable to parse the indicated file. Any attempt to execute the report will not run.

Action:
Check the JSP syntax against the documentation in the Help system.

REP-06204
The <rw:objects> tag cannot be found. Save operation aborted

Category:
Other

Cause:
The <rw:objects> tag was missing or invalid JSP syntax was found within the document.

Action:
Check the JSP syntax against the documentation in the Help system.

REP-06205
The ID attribute of tag {0} is not unique.

Category:
Other

Cause:
The report contains duplicate JSP ID attributes.

Action:
JSP ID attributes must be unique within a page. Change the ID of the tags that are not unique.

REP-06206
Tag {0} must be inside the rw:report tag.

Category:
Other

Cause:
A Reports JSP tag is outside the rw:report tag.

Action:
All Reports JSP tags must be inside the rw:report tag. Move the tag inside the rw:report tag. The easiest way to prevent this error is to move the </rw:report> tag to the bottom of the page.

REP-06207
Tag {0} tag has an invalid scope.

Category:
Other

Cause:
A Reports JSP tag is outside of the correct context.

Action:
Move the tag to its correct scope.

REP-06208
More than one rw:report tag is found. A report page can have only one rw:report tag.

Category:
Other

Cause:
The report contains more than one set of rw:report tags.

Action:
Add <rw:report> after the taglib lines at the top of the page. Add </rw:report> at the bottom of the page. Remove the extra rw:report tags.

REP-06209
Required Reports JSP tags are missing. The required Reports JPS tags have been added to the saved file.

Category:
Other

Cause:
When saving the JSP file, required Reports JSP tags were not found.

Action:
Click OK to add the required tags and save the file. Click Cancel to prevent Oracle Reports Builder from adding the tags, and not save the file.

REP-06210
Required Reports JSP tags are being added to the file.

Category:
Other

Cause:
If the file does not contain the required Reports JSP tags when it is first opened, Oracle Reports Builder adds the Reports JSP tags to the file loaded in memory. The original file on disk is not touched.

Action:
Click OK to continue working on the file.

REP-06211
The graph XML definition cannot be parsed.

Category:
Other

Cause:
Oracle Reports was unable to parse the XML definition of the graph.

Action:
Check the graph XML DTD against the Oracle BI Beans documentation.

REP-06212
The graph definition cannot be parsed.

Category:
Other

Cause:
Oracle Reports was unable to parse the definition of the graph.

Action:
Check the graph tag against the reports.tld.

REP-06213
A report level cursor cannot be created.

Category:
Other

Cause:
An internal error occurred when creating the report level cursor.

Action:
Contact Oracle Support Services if the problem persists.

REP-06214
A group cursor cannot be created.

Category:
Other

Cause:
An internal error occurred when creating the group cursor.

Action:
Contact Oracle Support Services if the problem persists.

REP-06215
An error occurred retrieving the next row from the cursor.

Category:
Other

Cause:
An internal error occurred when moving the group cursor to the next row.

Action:
Contact Oracle Support Services if the problem persists.

REP-06216
Unable to create related cursor

Category:
Other

Cause:
An internal error occurred when creating the related group cursor.

Action:
Contact Oracle Support Services if the problem persists.

REP-06217
No source specified for cursor

Category:
Other

Cause:
An internal error occurred. The cursor's source (that is, report for report level cursor, group for group cursor) is not specified.

Action:
Contact Oracle Support Services if the problem persists.

REP-06218
Value of unknown column {0} cannot be retrieved.

Category:
Other

Cause:
The column name is invalid.

Action:
Provide a valid column name.

REP-06219
Column {0} is not in the given cursor hierarchy.

Category:
Other

Cause:
The column does not belong to the cursor provided.

Action:
Modify the report so that the column belongs to given cursor hierarchy.

REP-06220
Value of column cannot be retrieved.

Category:
Other

Cause:
An internal error occurred when getting the value of the column.

Action:
Contact Oracle Support Services if the problem persists.

REP-06221
Column {0} cannot be found.

Category:
Other

Cause:
An internal error occurred when looking for a column.

Action:
Contact Oracle Support Services if the problem persists.

REP-06222
The column in the given cursor cannot be found.

Category:
Other

Cause:
The column does not belong to the cursor provided.

Action:
Modify the report so that column belongs to the given cursor.

REP-06223
Attempt to determine which cursor a column belongs to failed.

Category:
Other

Cause:
An internal error occurred when trying to find out to which cursor a column belongs, among a given list of cursors.

Action:
Contact Oracle Support Services if the problem persists.

REP-16500
This program can only be invoked as a CGI executable.

Category:
Other

Cause:
The Web CGI executable was invoked outside the Web Server context.

Action:
The CGI executable must be invoked by a Web server to work properly.

REP-16501
The Reports Web Agent key map file was not set up properly.

Category:
Other

Cause:
The key map file cannot be found at the location specified.

Action:
Check the file location.

REP-16504
The message subsystem cannot be initialized.

Category:
Other

Cause:
The Oracle Reports message file cannot be found or opened.

Action:
Check the installation. Verify that the Oracle Reports message file was installed properly.

REP-16505
A general error occurred during initialization.

Category:
Other

Cause:
A general error occurred.

Action:
Check the installation and availability of system resources.

REP-16506
The URL contains badly-formed escapes.

Category:
Other

Cause:
The submitted URL is badly formed.

Action:
See the URL rules in the Web Agent documentation.

REP-16507
The key is unrecognized.

Category:
Other

Cause:
The key map configuration is active, but the specified key in the URL is unrecognized, and the command line cannot be built.

Action:
Check the key value and keymap file setup and contents.

REP-16508
Key %s is unrecognized.

Category:
Other

Cause:
The key map configuration is active, but the specified key in the URL is unrecognized, and the command line cannot be built. This error may be due to bad URL syntax, or the key in the URL was not found in the key map file.

Action:
Check the key value and keymap file setup and contents.

REP-16509
Syntax errors are found in the key map file.

Category:
Other

Cause:
Syntax errors occurred in the key map file.

Action:
Check the key map file contents (see Web Agent documentation for rules). Check a definition of submitted key.

REP-16510
Usage in incorrect.

Category:
Other

Cause:
This is a generic error for a non-verbose run.

Action:
Enable verbocity and check the real message.

REP-16511
The URL contains too many parameters.

Category:
Other

Cause:
The URL contains too many parameters (it is too long).

Action:
Use a shorter URL or the key map file to shorten the URL.

REP-16512
out of memory

Category:
Memory

Cause:
There is not enough memory to perform the operation.

Action:
Verify that enough system resources are available.

REP-16513
Communication with the Reports Server is lost.

Category:
Other

Cause:
Reports Server is not answering.

Action:
Verify that Reports Server is up and the tnsnames.ora network setup has a correct entry for it.

REP-16514
The report cannot be run.

Category:
Other

Cause:
This is a generic error for a report run failure.

Action:
See the detailed error message from Reports Server.

REP-16515
The report output cannot be accessed.

Category:
Other

Cause:
The Web Agent cannot access Reports Server run output.

Action:
Check the Web Agent setup (especially WEBLOC variable).

REP-16516
The Reports Server is being shut down.

Category:
Other

Cause:
Reports Server is going down.

Action:
Try again later.

REP-16517
The Oracle Reports job is canceled upon user request.

Category:
Other

Cause:
The Oracle Reports job was canceled.

Action:
Try again if necessary.

REP-16518
The Reports Engine terminated abnormally.

Category:
Other

Cause:
The Reports Engine had problem with the report.

Action:
Contact the Reports Server administrator.

REP-16519
The Oracle Reports job has terminated with an error.

Category:
Other

Cause:
This is a generic error message for report run error.

Action:
See the detailed error message from Reports Server.

REP-16520
An error occurred while queuing a job to Reports Server.

Category:
Other

Cause:
An error occurred while enqueing report to run.

Action:
Try again later.

REP-16521
An error occurred while parsing the Reports Server command line.

Category:
Other

Cause:
An error occurred while attempting to run a report and process a command line.

Action:
Contact the Reports Server administrator.

REP-16522
The Reports Server name is not specified.

Category:
Other

Cause:
An error occurred while attempting to run a report and process a command line.

Action:
Contact the Reports Server administrator. Check the command line for a server name.

REP-16523
A report name is not specified.

Category:
Other

Cause:
An error occurred while attempting to run a report and process a command line.

Action:
Contact the Reports Server administrator. Check the command line for a report name.

REP-16524
A database logon is not specified.

Category:
Other

Cause:
An error occurred while attempting to run a report and process a command line.

Action:
Contact the Reports Server administrator. Check the command line for database logon.

REP-16525
The scheduling command cannot be interpreted.

Category:
Other

Cause:
An error occurred while attempting to run a report and process a command line.

Action:
Contact the Reports Server administrator. Check the SCHEDULE parameter.

REP-16526
The time tolerance cannot be interpreted.

Category:
Other

Cause:
An error occurred while attempting to run a report and process a command line.

Action:
Contact the Reports Server administrator. Check the TOLERANCE parameter.

REP-16527
The Parameter Form type is invalid.

Category:
Other

Cause:
An error occurred while attempting to run a report and process a command line.

Action:
Contact the Reports Server administrator. Check the PARAMFORM parameter.

REP-16528
An error occurred while communicating with the Reports Server.

Category:
Other

Cause:
A communication problem occurred.

Action:
Try again later.

REP-16529
The job cannot be killed.

Category:
Other

Cause:
This is a generic message for job kill failure.

Action:
Investigate why the job cannot be killed.

REP-16530
The job ID is invalid.

Category:
Other

Cause:
The ID of the Reports Server job is invalid.

Action:
Verify the ID.

REP-16531
The job is already finished.

Category:
Other

Cause:
The ID of the Reports Server job is invalid.

Action:
Verify the ID.

REP-16532
The job is not done yet. Try again later.

Category:
Other

Cause:
The ID of the Reports Server job is invalid.

Action:
Verify the ID.

REP-16533
There are insufficient privileges to perform the requested action.

Category:
Other

Cause:
The ID of the Reports Server job is invalid.

Action:
Verify the ID and privileges.

REP-16534
Report output cannot be accessed.

Category:
Other

Cause:
The Oracle Reports output directory is not accessible.

Action:
Check the directory specification and the setup (REPORTS_WEBLOC or REPORTS_WEBLOC_TRANSLATED environment is probably invalid).

REP-16535
Report output cannot be accessed.

Category:
Other

Cause:
The Oracle Reports output directory is not accessible.

Action:
Check the directory specification and the setup (REPORTS_WEBLOC or REPORTS_WEBLOC_TRANSLATED environment is probably invalid).

REP-16537
Report output cannot be saved.

Category:
Other

Cause:
Report output of the returned name already exists in the Web directory.

Action:
Check the Web Agent setup (REPORTS_WEBLOC_TRANSLATED environment probably points to the same location as a Reports Server cache).

REP-16538
Report output was successfully printed.

Category:
Other

Cause:
The report was successfully run to the printer.

Action:
No action is needed.

REP-16539
Report output was successfully mailed.

Category:
Other

Cause:
The report was successfully run to mail.

Action:
No action is needed.

REP-16540
Report output was successfully written to the requested destination.

Category:
Other

Cause:
The report was successfully run to the requested destype.

Action:
No action is needed.

REP-16541
Log on before running the report.

Category:
Other

Cause:
It is necessary to log on before running the report.

Action:
Log on again.

REP-16542
Report output was successfully written to the InterOffice repository.

Category:
Other

Cause:
The report was successfully run to the InterOffice repository.

Action:
No action is needed.

REP-16543
The report output cannot be accessed.

Category:
Other

Cause:
The Oracle Reports output directory is not accessible.

Action:
Check the directory specification. Check the setup (REPORTS_VIRTUAL_MAP, REPORTS_PHYSICAL_MAP and REPORTS_SHARED_CACHE environment is probably invalid.)

REP-16544
The report output cannot be accessed.

Category:
Other

Cause:
The Oracle Reports output directory is not accessible.

Action:
Check directory specification. Check the setup (REPORTS_VIRTUAL_MAP, REPORTS_PHYSICAL_MAP and REPORTS_SHARED_CACHE environment is probably invalid.)

REP-20091
Save the current document before disconnecting from the database?

Category:
Other

Cause:
An open document is stored in the database. If disconnected from the database, changes cannot be saved to the database.

Action:
Select Yes to save the document before disconnecting from the database; the document remains open to reconnect if desired and save it to the database again. Select No to disconnect from the database without saving the document; the document remains open. Select Cancel to remain connected to the database without saving; once again, the document remains open.

REP-20099
Printer changed while previewing. Printer font remapping could cause truncation. Continue with printing?

Category:
Other

Cause:
In the time between running the report and selecting Print from the Previewer, the default printer has changed.

Action:
Select Yes to print anyway. Select No to halt printing, then close the report and either reset the printer and run the report again, or simply run it again to format it for the current printer.

REP-20128
The report was not run with DESTYPE=PREVIEW. Screen font remapping could cause truncation. Continue with printing?

Category:
Other

Cause:
Print was selected from the Previewer, but specified Screen instead of Preview, which formats the report as though using printer fonts and provides a more accurate view of the report's printed output.

Action:
Select Yes to print anyway. Select No to halt printing. Then close the report and run it again while specifying Preview to format it for the printer.

REP-20129
Opening a report saved with a newer version of Oracle Reports Builder. Functionality may be lost. Continue?

Category:
Other

Cause:
An attempt was made to open a report with a version of Oracle Reports Builder older than the version used to create the report. If the report uses functionality unavailable in the older version, that functionality will be eliminated from the report.

Action:
To avoid losing functionality, do not open the report until after upgrading to the most recent version of Oracle Reports Builder.

REP-20135
A layout does not exist. Create a default layout?

Category:
Other

Cause:
An attempt was made to run the report after creating a data model but before creating a layout.

Action:
Select Yes to create a default layout using the Report Wizard. Select No to run the report without a layout.

REP-20136
The region chosen for the default layout is too small. Extend the region to page boundaries?

Category:
Other

Cause:
The Report Block tool was used to draw a region for a layout that was not large enough to accommodate the settings specified in the Report Block Wizard.

Action:
Select Yes to have Oracle Reports Builder extend the possible range of the layout to the boundaries of a report page, or select No and change the settings in the Report Block Wizard to shrink the size of the layout.

REP-20138
Oracle Reports Builder tables may not be installed in the database.

Category:
Other

Cause:
Oracle Reports Builder was not able to access its tables in the database.

Action:
Inform the database administrator that the Oracle Reports Builder tables were not successfully installed in the database.

REP-20139
New Parameter Form layout will not fit its current size. Increase the number of pages to fit?

Category:
Other

Cause:
The new Parameter Form is too big to fit on the number of pages specified for the Parameter Form in the Report Properties dialog box.

Action:
Either select Yes to have Oracle Reports Builder increase the number of pages in the Parameter Form, or select No and change the settings in the Report Properties dialog to enlarge the Parameter Form.

REP-20144
Opening a report saved with a newer version of Oracle Reports Builder. Functionality may be lost.

Category:
Other

Cause:
An attempt was made to open a report with a version of Oracle Reports Builder older than the version used to create the report. If the report uses functionality unavailable in the older version, that functionality will be eliminated from the report.

Action:
To avoid losing functionality, do not open the report until after upgrading to the most recent version of Oracle Reports Builder.

REP-20146
This action may invalidate references to columns in the referenced object.

Category:
Other

Cause:
Collapsing a Database Ref, Database Nested Table, or Database Varray column invalidates any external use of the referenced columns. for example, in PL/SQl Program Units or in Summary Columns.

Action:
To use the referenced columns, do not collapse the Database Ref, Database Nested Table, or Database Varray columns referencing them.

REP-20147
A column link for this detail SQL query cannot be implemented. Converting to group link.

Category:
Other

Cause:
Oracle Reports Builder can only insert column to column links into supported SQL. It defaults to a group to group link in this case.

Action:
Manually insert the required link clause into the detail SQL query.

REP-20150
Page width of report {0} was changed to fit the font for a character cell as a consequence of font-mapping.

Category:
Other

Cause:
A character font has been substituted for a bitmapped font in the report, and the page width has been adjusted accordingly. A possible cause: a bitmapped report is being opened in the character-mode runtime engine.

Action:
To map the font to a specific font, edit the font alias file (uifont.ali or Oracle Font Aliases, depending on the platform) to map the fonts to the desired ones. Otherwise, no action is necessary.

REP-20151
Some fonts have been changed according to the mapping in the font aliases file.

Category:
Other

Cause:
One or more fonts saved with the report have been mapped to different ones, due to a change in platform, display, report destination, or mode.

Action:
To map the font to a specific font, edit the font alias file (uifont.ali or Oracle Font Aliases, depending on the platform) to map the fonts to the desired ones. Otherwise, no action is necessary.

REP-20160
An AutoRecovery file was detected. Recover unsaved changes for {0}?

Category:
Other

Cause:
Oracle Reports Builder can automatically recover unsaved report changes if it stops responding or there is a power failure.

Action:
Either select Yes to have Oracle Reports Builder recover unsaved report changes, or select No to ignore.

REP-20161
Unable to save AutoRecovery file, Autosave functionality would be disabled.

Category:
Other

Cause:
Oracle Reports Builder tried to write an AutoRecovery file and could not. The possible causes of this error include the following: Case 1: Lack of necessary privileges to write the file. Case 2: The file system does not have enough room for the file. Case 3: A system error made it impossible to open the file.

Action:
Either select OK to have Oracle Reports Builder to disable Autosave, or select Cancel to take the following actions to correct this error: If Case 1: Verify the privileges necessary to write the file. If Case 2: Make more room by deleting unnecessary files or expanding storage. If Case 3: Consult the operating system documentation or contact the system administrator.

REP-20190
Quit will terminate the current report, as well as any other pending reports.

Category:
Other

Cause:
A request to exit the Reports Server or Reports Background Engine was issued while one or more reports are still executing or awaiting execution.

Action:
To finish report execution, cancel the operation. Otherwise, accept the warning dialog.

REP-20191
Cannot exit Windows when this program is running. Close the Reports Background Engine and exit Windows.

Category:
Operating System

Cause:
The Reports Background Engine requires Windows, but a request was issued to exit Windows while the Reports Background Engine is still running.

Action:
Exit the Reports Background Engine before exiting Windows.

REP-25206
Converting {0} to {1} failed.

Category:
Other

Cause:
The most likely cause of this error is that the source type specified was incorrect.

Action:
Ensure that the source file is of the specified source type.

REP-25207
Invalid conversion: stype and dtype are not of the same document type.

Category:
Other

Cause:
An attempt was made to convert a document of one type to another type; that is, an attempt to convert one of the possible report files to a PL/SQL file, or vice versa.

Action:
Ensure that the source and destination of theconversion are the same type of document.

REP-25401
User exit .DLL file {0} cannot be found.

Category:
Other

Cause:
The report attempted to execute a user exit, but the user exit .DLL file could not be located. This file typically resides in: the current directory the Windows directory (typically \ \WINDOWS) the Windows system directory (typically \\WINDOWS\\SYSTEM) the directory containing the executable file for the current task the directories listed in the PATH environment variable the list of directories mapped in a network

Action:
Locate the specified .DLL file and place it in one of the directories listed above.

REP-25402
An internal error occurred attempting to locate user exit .DLL file {0} within file {1}

Category:
Other

Cause:
The report attempted to execute a user exit, but certain functions used to locate and execute user exits cannot be located in the user exit .DLL file. This means that the user exit .DLL was built incorrectly, because these functions are located in a .OBJ file shipped with Oracle Reports Builder, which should always be linked into the user exit .DLL.

Action:
Rebuild the specified user exit .DLL correctly.

REP-31681
Connecting to a different database may invalidate existing data model.

Category:
Data

Cause:
Only one connection to a database is valid at a time. If a connection is established to different database, the existing data model may not be valid afterward.

Action:
To keep the existing data model valid, do not reconnect to a different database unless the queries are compatible with the new database connection.

REP-31700
The report definition is incomplete, or the query does not have break groups. Cannot run the Web Wizard.

Category:
Other

Cause:
The report definition was not completed before running the Web Wizard. To run the Web Wizard, the report definition must contain a Data Model with multiple groups and a valid Paper Layout.

Action:
Create at least one query with multiple groups and default the layout using the Report Wizard.

REP-31800
Image file {0} cannot be found.

Category:
Other

Cause:
Oracle Reports Builder could not locate one of its image files. Possible causes of this error include: Case 1: The image file does not exist Case 2: The image file is in the wrong place. Case 3: The environment is not configured properly.

Action:
Take the following actions to correct this error: If Case 1: Verify that the image file is present. If Case 2: Verify that the image file is in the proper directory. If Case 3: Verify that the environment is set correctly. On UNIX, verify that the proper environment variable is set, and on MS Windows check the file oracle.ini.

REP-31801
Image {0} specified in the template cannot be found.

Category:
Other

Cause:
Oracle Reports Builder could not locate the image corresponding to the chosen templage. Possible causes of this error include: Case 1: The image file does not exist Case 2: The image file is in the wrong place. Case 3: The environment is not configured properly.

Action:
Take the following actions to correct this error: If Case 1: Verify that the image file is present. If Case 2: Verify that the image file is in the proper directory. If Case 3: Verify that the

environment is set correctly. On UNIX, verify that the proper environment variable is set, and on MS Windows check the file oracle.ini.

REP-31802
Enter a SQL statement on this page.

Category:
Other

Cause:
In order for the wizard to create the report, a valid SQL text must exist.

Action:
Enter a SQL statement.

REP-31803
SQL text cannot be checked due to no database connection.

Category:
Other

Cause:
The wizard requires a connection to a database in order to check the SQL text.

Action:
Connect to a database by typing in a login string whenever the Connect dialog is shown. Confirm logon information with the database administrator.

REP-31804
The SQL is OK.

Category:
Other

Cause:
The wizard has checked the SQL text against the database and has confirmed that it will work.

Action:
No changes are needed to the SQL text.

REP-31805
Break level {0} has no valid break columns.

Category:
Other

Cause:
Each break level must contain at least one valid break column. A break column cannot be a summary or placeholder column. Nor can it have a data type of Raw, Longraw, or Long.

Action:
Provide at least one valid break column for the break level or move all columns that are currently in this break level to another level which contains a valid break column.

REP-31806
All fields cannot be designated to be break fields.

Category:
Other

Cause:
All fields were chosen to be break fields. Each break field designated groups the data of the fields that are not break fields. With no non-break fields, this situation is invalid.

Action:
Designate at least one field to be a non-break field. For example, remove all break fields from the highest numbered break level (that is, from the bottom of the list of break fields).

REP-31807
Template file {0} cannot be found.

Category:
Other

Cause:
Oracle Reports Builder could not locate the template file with the given name. Possible causes of this error include: Case 1: The template file does not exist. Case 2: The template file is in the wrong place. Case 3: The environment is not configured properly.

Action:
Take the following actions to correct this error: If Case 1: Verify that the template file is present. If Case 2: Verify that the template file is in the proper directory. If Case 3: Verify that the environment is set correctly. On UNIX, verify that the proper environment variable is set, and on MS Windows check the file oracle.ini.

REP-31808
A SQL statement must be entered.

Category:
Other

Cause:
A SQL statement was not entered for the wizard to generate a report.

Action:
Enter a SQL statement in the wizard tab.

REP-31809
At least one field to display must be chosen.

Category:
Other

Cause:
No field has been selected to display.

Action:
Select some fields to display.

REP-31810
At least one break group must be created.

Category:
Other

Cause:
The current report style needs breaks groups.

Action:
Create some break groups.

REP-31811
At least one matrix row must be selected.

Category:
Other

Cause:
Nothing has been selected as matrix rows.

Action:
Select some columns as matrix rows.

REP-31812
At least one matrix column must be selected.

Category:
Other

Cause:
Nothing has been selected as matrix columns.

Action:
Select some columns as matrix columns.

REP-31813
At least one matrix cell must be selected.

Category:
Other

Cause:
Nothing has been selected as matrix cells.

Action:
Select some columns as matrix cells.

REP-31814
At least one matrix break must be selected.

Category:
Other

Cause:
Nothing has been selected as matrix breaks.

Action:
Create some matrix break groups.

REP-31815
At least one field must be displayed per group.

Category:
Other

Cause:
This problem is due to: 1) This field has been specified as a group field. 2) The group of this field has been defaulted, and this field is the only one that has been marked as "to be defaulted" in its group.

Action:
1) If this field has been specified as a group field, go to the group page to deselect this field. 2) If the group of this field has been default, go to the group page to deselect that group.

REP-31816
Groups to be defaulted must be selected.

Category:
Other

Cause:
No group has been selected to be defaulted.

Action:
Select groups to be defaulted.

REP-31817
At the top of the group. Cannot move up.

Category:
Other

Cause:
This column is at the top of its group.

Action:
Do not try to move this column up.

REP-31818
At the bottom of the group. Cannot move down.

Category:
Other

Cause:
This column is at the bottom of its group.

Action:
Do not try to move this column up.

REP-31819
Report level columns cannot be reordered.

Category:
Other

Cause:
Report level columns do not have the POS attribute.

Action:
Set where to display the report level columns in the Paper Layout editor.

REP-31820
Selected groups have no columns in them.

Category:
Other

Cause:
Selected groups have no columns in them, so no report can be generated.

Action:
Select some other groups.

REP-31821
There is no text specified in the text editor.

Category:
Other

Cause:
The text for a mailing label or form letter report is empty.

Action:
Type some text in the text editor.

REP-31822
One group must be selected.

Category:
Other

Cause:
No group has been selected.

Action:
Go to the group page and select one group.

REP-31823
One and only one group must be selected.

Category:
Other

Cause:
There is more than one group selected.

Action:
Select one and only one group.

REP-31824
Another group must be selected since there are no columns in the selected group.

Category:
Other

Cause:
There are no columns in the selected group.

Action:
Select another group that has columns.

REP-31825
Cancel the wizard and fix the problem in report editors.

Category:
Other

Cause:
The data model is invalid or the default region is too small.

Action:
Fix the problem in the Data Model editor or Paper Layout editor.

REP-31826
A custom template file name is not specified.

Category:
Other

Cause:
A custom template is selected, but no template file name is specified.

Action:
Type a custom template file name, or click Browse button to navigate to it.

REP-31827
Invalid print direction or illegal defaulting of page level summary column.

Category:
Other

Cause:
The print direction against one or more groups is invalid for the requested default style, or page level summary column was selected to be defaulted (page level summaries are not supported within defaulting).

Action:
Alter the print direction against the group or the default style, or deselect all page level summaries.

REP-31828
The query definition is invalid.

Category:
Other

Cause:
The query is not properly defined.

Action:
Define a valid query.

REP-31906
This type of graph requires more categories than have been selected.

Category:
Other

Cause:
The number of categories required for a graph depends on the type of graph selected. This type of graph requires more categories than were selected.

Action:
Select the minimum number of categories required by the type of graph selected in a previous panel.

REP-31907
This type of graph requires more data columns than have been selected

Category:
Data

Cause:
The number of data columns required for this graph depends on the type of graph selected. This type of graph requires more data columns than were selected.

Action:
Select the minimum number of data columns required by the type of graph selected in a previous panel.

REP-31908
The Data Model has changed. Reselect categories and data for the created graph.

Category:
Data

Cause:
The data model has been changed for an existing graph.

Action:
Reselect the categories and data for the graph.

REP-31909
This type of graph requires %s categories.

Category:
Other

Cause:
The number of categories required for a graph depends on the type of graph selected. This type of graph requires %s categories.

Action:
Select the minimum number of categories required by the type of graph selected in a previous panel.

REP-31910
This type of graph requires %s data columns.

Category:
Data

Cause:
The number of data columns required for this graph depends on the type of graph selected. This type of graph requires %s data columns.

Action:
Select the minimum number of data columns required by the type of graph selected in a previous panel.

REP-31950
An error occurred in the Oracle Reports Builder graph support.

Category:
Other

Cause:
An error occurred initializing the Graph Wizard.

Action:
Verify that all components are installed properly. Restart the product.

REP-31951
The Graph Wizard cannot be initialized.

Category:
Other

Cause:
The Graph Builder library could not be initialized.

Action:
Verify that the Graph Wizard and Graphics Runtime are properly installed and that there are enough system resources available.

REP-31952
The Graph Wizard cannot be initialized due to incorrect version of libraries.

Category:
Other

Cause:
The Graph Builder library could not be initialized.

Action:
Verify that the Graph Wizard libraries are properly installed and that there are enough system resources available.

REP-31953
An error occurred in the Graph Wizard.

Category:
Other

Cause:
The Graph Builder library could not be initialized.

Action:
Verify that the Graph Wizard libraries are properly installed and that there are enough system resources available.

REP-31954
An error occurred in the Graph Wizard user interface.

Category:
Other

Cause:
The Graph Wizard failed to load properly.

Action:
Verify that the Graph Wizard libraries are properly installed and that there are enough system resources available.

REP-31955
An error occurred in the graph runtime executable while attempting to create a graph.

Category:
Other

Cause:
The Graph Builder failed to build the graph.

Action:
Verify that the Graph Wizard libraries are properly installed and that there are enough system resources available.

REP-31980
Incorrect field mapping is specified. The graph will not be generated.

Category:
Other

Cause:
Fields for both category and value axes were not specified in the Graph Wizard.

Action:
Reenter the Graph Wizard and specify fields for both Category and Value axes.

REP-31981
The Data Model is empty or invalid.

Category:
Data

Cause:
The Graph Wizard was invoked on an empty report.

Action:
Create report (at least a data model) and try again.

REP-32600
An unexpected error occurred. Aborting.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-32601
The report already exists in a translation file.

Category:
Other

Cause:
An attempt was made to overwrite an existing translation file.

Action:
Select a different name for the translation file.

REP-32602
Oracle Reports Builder cannot be initialized.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-32603
The VGS system cannot be initialized.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-32604
A fatal error occurred loading report {0}. Check version.

Category:
Other

Cause:
The specified report cannot be loaded.

Action:
Verify that the correct version of the report is being opened.

REP-32605
The report file cannot be opened for reading.

Category:
Other

Cause:
The report file is unreadable.

Action:
Check the read permission of the report file.

REP-32606
File {0} cannot be opened for reading.

Category:
Other

Cause:
The specified file cannot be opened.

Action:
Verify that the file exists and is readable.

REP-32607
The translation builder tree does not exist.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-32608
Translations for that language do not exist.

Category:
Other

Cause:
The Translation Manager cannot translate into the given target language.

Action:
Verify that the target language is supported.

REP-32609
This is not a valid report tree.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-32610
Source data file {0} does not match.

Category:
Data

Cause:
The translation file being merged into the report was not created from the selected report.

Action:
Merge the translation file into the original report.

REP-32612
The string for the base language cannot be merged.

Category:
Other

Cause:
An attempt was made to merge the untranslated strings back into the original report.

Action:
Translate the strings in the translation file and try again.

REP-32613
A matching VGS string in NX file cannot be found.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-32614
Successfully merged strings for language {0}.

Category:
Other

Cause:
The operation was completed with no errors.

Action:
No action is necessary.

REP-32615
The merge operation failed.

Category:
Other

Cause:
The merge operation encountered errors.

Action:
Check the log file for more information.

REP-32616
Translations in NX file cannot be found.

Category:
Other

Cause:
The translation file does not contain translated strings.

Action:
Verify that the correct translation file is used for the given report.

REP-32617
The NX file is corrupt.

Category:
Other

Cause:
An abnormal condition was encountered.

Action:
For assistance, contact Oracle Support Services.

REP-32618
The NX file cannot be opened for reading.

Category:
Other

Cause:
The translation file cannot be opened.

Action:
Verify that the file exists and is readable.

REP-32750
The data of image {0} cannot be unpacked. The image has been removed.

Category:
Data

Cause:
Case 1: The image data is corrupted. Case 2: REPORTS_DEFAULT_DISPLAY is set to YES and the image format used is not supported.

Action:
Take the following actions to correct this error: If Case 1: Import the image again. If Case 2: Verify that the image format is one of the supported formats: GIF, JPEG, JPG, PNG, BMP.

REP-32751
Some text segments are missing.

Category:
Other

Cause:
Text segments cannot be found for some boilerplate text. The report could be corrupted.

Action:
Check the boilerplate text objects in the report. Remove suspicious ones and create replacements for them.

REP-34202
A value must be entered.

Category:
Other

Cause:
No value has been entered.

Action:
Enter a value.

REP-34203
WARNING: The user modified Format Trigger will be overwritten. Continue?

Category:
Other

Cause:
Format trigger has been modified.

Action:
Click Yes to overwrite the user modified trigger. Click No or Cancel to retain the modified trigger.

REP-34205
At least one condition must be specified.

Category:
Other

Cause:
No condition was specified in the Format Exception dialog box.

Action:
Specify at least one condition.

REP-34300
No distribution list is available.

Category:
Other

Cause:
No distribution target has been specified for the report.

Action:
Create a distribution list.

REP-34301
The value for the field is invalid.

Category:
Other

Cause:
An invalid value or no value has been entered for the field.

Action:
Enter a valid value.

REP-34302
The destination format is not compatible with the runtime mode.

Category:
Other

Cause:
The destination format must be compatible with the current mode for running the report. Likewise, the destination format must be compatible with all other destination formats in the report. There is no support for mixing bitmap output with character mode output.

Action:
Ensure all the destination formats are compatible with either character or bitmap output modes.

REP-34305
The keyword setting for the destid={0} is invalid.

Category:
Other

Cause:
Keyword settings are incorrect in the distribution file.

Action:
Alter the distribution file to ensure that all entries have valid values.

REP-34306
No distribution ID has been specified for the destination.

Category:
Other

Cause:
In the distribution file, the ID for the destination is missing.

Action:
Add a destination ID to the destination line. For example: Dest1:

REP-34307
The destination ID is not unique.

Category:
Other

Cause:
In the distribution file, the ID for the destination is not unique.

Action:
Add a unique destination ID for the entry.

REP-34308
Reference parameter {0} in the distribution list is invalid.

Category:
Other

Cause:
The reference parameter in the distribution list refers to a wrong group.

Action:
Repeat on the same group as that of the reference parameter.

REP-34309
A reference parameter is not allowed in a Report-level distribution list.

Category:
Other

Cause:
A reference parameter was found in a Report-level distribution list.

Action:
Remove the reference paramter distribution item from the Report-level distribution list.

REP-34310
A reference parameter is not allowed in a distribution list for XML destination files.

Category:
Other

Cause:
An XML destination cannot have a reference parameter in the distribution list.

Action:
Remove the reference parameter for the XML file destination from the distribution list.

REP-34311
The XSL transformation file cannot be found.

Category:
Other

Cause:
The XSL transformation file distribution.xsl could not be located.

Action:
Ensure that the XSL file is placed in ORACLE_HOME/reports/conf.

REP-34312
An error occurred in XSL template.

Category:
Other

Cause:
An error occurred when applying XSL transformation. This could be due to an error in the XSL file.

Action:
Check the XSL file and ensure the transformations are correct.

REP-34313
The external file {0} specified in destination {1} cannot be found.

Category:
Other

Cause:
An external file specified in the distribution list was not found.

Action:
Verify the correct path of the external file specified.

REP-34314
The foreach tag cannot be used before both the mail and attach tags at destination {0}.

Category:
Other

Cause:
The foreach tag was used before both the mail tag and the attach tag.

Action:
Correct the entry in the XML distribution file to use a single level of foreach tag.

REP-34315
The instance attribute cannot be used without a foreach tag at destination {0}.

Category:
Other

Cause:
The instance attribute was used without an enclosing foreach tag.

Action:
Correct the entry in the XML distribution file to use a foreach tag at the appropriate level.

REP-34316
Reference parameters cannot be used without a foreach tag in destination {0}.

Category:
Other

Cause:
Reference parameters were used without a foreach tag.

Action:
Correct the entry in the XML distribution file to use a foreach tag appropriately.

REP-34317
The instance attribute cannot be used if 'srctype' is not 'report' in destination {0}.

Category:
Other

Cause:
The instance attribute was used for a body or attach tag whose source is not a report section.

Action:
Correct the entry in the XML distribution file to remove the instance attribute.

REP-34318
The foreach tag cannot be used if 'srctype' is not 'report' in destination {0}.

Category:
Other

Cause:
A foreach tag was used before an attach tag whose source is not a report section.

Action:
Correct the entry in the XML distribution file to remove the foreach tag.

REP-34319
An unknown report section {0} was specified as the source in destination {1}.

Category:
Other

Cause:
The src attribute in the include tag does not specify a valid report section.

Action:
Correct the entry in the XML distribution file to use a valid report section. The valid report sections can be any one of 'headerSection', 'mainSection', 'trailerSection', or 'report'.

REP-34320
Report sections used in destination {1} do not repeat on the same group.

Category:
Other

Cause:
The report sections used in include tags do not repeat on the same group.

Action:
Modify the report definition so that all the sections used repeat on the same group. Use only those report section combinations that repeat on the same group.

REP-34321
Only one external file can be specified in the body or attachment at destination {0}.

Category:
Other

Cause:
More than one external file was specified for the corresponding body or attach tag. Each body or attach tag whose srctype is file, can have only one include tag referring to an external file.

Action:
Correct the entry in the XML distribution file and specify only one external file for the body or attach tag.

REP-34322
Inline text for body or attach tag for destination {0} can be specified only if 'srctype' is 'text'.

Category:
Other

Cause:
Inline text was specified for a body or an attach tag whose 'srctype' is not 'text'.

Action:
Correct the entry in the XML distribution file and specify the correct 'srctype'.

REP-34323
Tag {0} specified for destination {1} cannot be empty.

Category:
Other

Cause:
An empty tag was encountered. Only the include and the property tags can be empty. All other tags must have at least one child.

Action:
Correct the entry in the XML distribution file by either removing the empty tag or inserting the appropriate child tag for it.

REP-34324
Inline text is missing when 'srctype' is 'text' at destination {0}.

Category:
Other

Cause:
Inline text was not specified for a body or an attach tag whose 'srctype' is specified as 'text'.

Action:
Correct the entry in the XML distribution file by specifying the appropriate srctype for the corresponding body or attach tag. If the 'srctype' should be 'text', replace the include tag with inline text.

REP-34325
A reference parameter is not allowed in a distribution list for DelimitedData destination files.

Category:
Other

Cause:
DelimitedData destination cannot have a reference parameter in the distribution list.

Action:
Remove the reference parameter for the DelimitedData file destination from the distribution list.

REP-34326
SPREADSHEET format is not supported in distribution.

Category:
Other

Cause:
SPREADSHEET destination cannot be used in distribution.

Action:
Remove the SPREADSHEET destination from the distribution XML file.

REP-34501
A Web design tool is not registered.

Category:
Other

Cause:
The mail destination specified is too long. Destination names must be less than 1024 characters. The PREFS.ORA file does not contain an entry for a Web design tool.

Action:
Specify a mail destination the 'To' field that is less than 1024 characters. Add an entry for the Web design tool.

REP-34502
The Web design tool registered cannot be found or run.

Category:
Other

Cause:
The Web design tool does not exist, or the file exists but cannot run.

Action:
Correct the PREFS.ORA file and move the Web design program to the correct directory.

REP-34551
Feature {0} is deprecated. See the Oracle Reports documentation for more information.

Category:
Other

Cause:
The feature is deprecated.

Action:
See the Oracle Reports documentation on the Oracle Technology Network (OTN).

REP-34552
The Oracle Graphics Graph in this document will not be saved.

Category:
Other

Cause:
There are one or more obsolete Oracle Graphics graphs in this document that will not be saved.

Action:
Replace the Oracle Graphics graphs with new graphs generated with the Graph Wizard.

REP-35000
The output image format specified is not supported.

Category:
Other

Cause:
The output image format specified on the command line is not supported by Oracle Reports.

Action:
Specify one of the supported output image formats. Refer to the Oracle Reports online help for a list of supported output image formats.

REP-35001
An interanl error occurred writing the image.

Category:
Other

Cause:
The image stream may be invalid or corrupt. A failure occurred while reading the image data from the image stream.

Action:
For assistance, contact Oracle Support Services.

REP-35002
The Reports Toolkit System is not available.

Category:
Other

Cause:
An error occurred initializing the Reports Toolkit System. The required Java classes were not found.

Action:
For assistance, contact Oracle Support Services.

REP-35003
CGM or OGD format cannot be converted to image for HTML/HTMLCSS output.

Category:
Other

Cause:
CGM or OGD is used in the report. It is not supported when Display is not available.

Action:
Remove the OGD or CGM image used in the report. Set DISPLAY and REPORTS_DEFAULT_DISPLAY to NO. Verify that the image format is one of the supported formats: GIF, JPEG, JPG, PNG, BMP.

REP-35004
The Oracle Reports Font Toolkit Subsystem is not available.

Category:
Other

Cause:
An error occurred while initializing the Oracle Reports Font Toolkit Subsystem. The required Java classes were not found.

Action:
For assistance, contact Oracle Support Services.

REP-35503
PDFOWNER and PDFUSER cannot have the same value.

Category:
Other

Cause:
PDFOWNER and PDFUSER cannot be same.

Action:
Specify different values for PDFUSER and PDFOWNER.

REP-50000
A generic error occurred while running the job.

Category:
Other

Cause:
A generic error occurred while running the job.

Action:
For assistance, contact Oracle Support Services.

REP-50001
The server is initializing.

Category:
Other

Cause:
Reports Server is initializing.

Action:
Wait until the Reports Server is ready to serve requests.

REP-50002
The server is shutting down.

Category:
Other

Cause:
The Reports Server is shutting down.

Action:
Restart the Reports Server.

REP-50003
The command line is invalid: {0}.

Category:
Other

Cause:
An invalid command line was submitted.

Action:
Refer to the Oracle Reports documentation for command-line arguments and syntax.

REP-50004
No report is specified on the command line.

Category:
Other

Cause:
There is no report name specified on the command line.

Action:
Specify the name of the report on the command line.

REP-50005
No USERID is specified on the command line.

Category:
Other

Cause:
There is no USERID keyword specified on the command line.

Action:
Specify USERID on the command line as part of the database connection information.

REP-50006
The SCHEDULE argument is invalid on the command line: {0}.

Category:
Other

Cause:
The SCHEDULE argument value on the command line is not correct.

Action:
Refer to the Oracle Reports documentation for the correct SCHEDULE argument syntax.

REP-50007
The TOLERANCE argument is invalid on the command line: {0}.

Category:
Other

Cause:
The TOLERANCE argument value on the command line is not correct.

Action:
Refer to Oracle Reports documentation for correct TOLERANCE argument syntax.

REP-50008
The report is successfully submitted.

Category:
Other

Cause:
The report is successfully submitted to the Reports Server.

Action:
No action required.

REP-50009
The report is successfully run.

Category:
Other

Cause:
The report ran successfully in the Reports Server.

Action:
No action required.

REP-50108
The job is waiting in the queue.

Category:
Other

Cause:
The job is waiting in the queue to be executed.

Action:
No action required.

REP-50109
The report is opening to run.

Category:
Other

Cause:
Opening the report to run.

Action:
No action required.

REP-50110
Report {0} is running.

Category:
Other

Cause:
Running the specified report.

Action:
No action required.

REP-50111
Report {0} finished successfully.

Category:
Other

Cause:
The report has finished successfully.

Action:
No action required.

REP-50112
The report terminated with error: {0}.

Category:
Other

Cause:
The report terminated with the stated error.

Action:
Correct the error and rerun the report.

REP-50113
The engine crashed.

Category:
Other

Cause:
The engine crashed due to an internal error.

Action:
For assistance, contact Oracle Support Services

REP-50114
The job is canceled upon user request.

Category:
Other

Cause:
The job was canceled at the user's request.

Action:
No action required.

REP-50115
The job is canceled as the server is shutting down.

Category:
Other

Cause:
The job was canceled because the Reports Server is shutting down.

Action:
No action required.

REP-50116
The job execution failed and is waiting for retry.

Category:
Other

Cause:
The job execution has failed and waiting to be retried.

Action:
No action required.

REP-50117
The job is sending output.

Category:
Other

Cause:
The job is sending output to specified destinations.

Action:
No action required.

REP-50118
Report execution is initialized.

Category:
Other

Cause:
Initializing report execution.

Action:
No action required.

REP-50119
A Before Report trigger is running.

Category:
Other

Cause:
The report is running a Before Report trigger.

Action:
No action required.

REP-50120
A Between Pages trigger is running.

Category:
Other

Cause:
The report is running a Between Pages trigger.

Action:
No action required.

REP-50121
An After Report trigger is running.

Category:
Other

Cause:
The report is running an After Report trigger.

Action:
No action required.

REP-50122
A Before Parameter Form trigger is running.

Category:
Other

Cause:
The report is running a Before Parameter Form trigger.

Action:
No action required.

REP-50123
An After Parameter Form trigger is running.

Category:
Other

Cause:
The report is running an After Parameter Form trigger.

Action:
No action required.

REP-50124
Page {0} is formatting.

Category:
Other

Cause:
Oracle Reports is formatting the specified page.

Action:
No action required.

REP-50125
An internal exception occurred: {0}.

Category:
Other

Cause:
Oracle Reports encountered an internal exception.

Action:
For assistance, contact Oracle Support Services

REP-50126
File {0} cannot be opened for writing.

Category:
Other

Cause:
Oracle Reports cannot open the specified file for writing.

Action:
Check the write permission of the file, or of the directory in which the file is stored.

REP-50127
File {0} cannot be written to.

Category:
Other

Cause:
Oracle Reports cannot write content to the specified file.

Action:
Check available disk space to verify that that there is enough space to write the file. Verify that no other applications are writing to the same file.

REP-50131
An attempt to bind to {0} failed.

Category:
Other

Cause:
Binding to Reports Server failed.

Action:
Verify that the Reports Server is running and that it is accessible from this machine.

REP-50133
The job has been transferred to {0}, the new job ID is {1}.

Category:
Other

Cause:
The job has been transferred to another server.

Action:
No action required.

REP-50134
Cache subitem {0} does not exist.

Category:
Other

Cause:
An internal error occurred. Some of the report output is deleted unexpectedly.

Action:
Rerun the job to get the correct output.

REP-50135
Class {0} cannot be located.

Category:
Other

Cause:
Oracle Reports cannot locate the specified class.

Action:
Verify that the specified class is in the CLASSPATH and REPORTS_CLASSPATH.

REP-50136
An error occurred reading the input stream: {0}.

Category:
Other

Cause:
Oracle Reports cannot read an input stream due to the stated error.

Action:
Correct the error and rerun the report.

REP-50137
The input stream cannot be closed: {0}.

Category:
Other

Cause:
Oracle Reports cannot close the input stream due to the stated error.

Action:
For assistance, contact Oracle Support Services

REP-50138
A mail server is not available.

Category:
Other

Cause:
There is no mail server specified in Reports Server configuration file.

Action:
Add a <mail> element with a server attribute to the Reports Server configuration file.

REP-50139
File {0} cannot be deleted.

Category:
Other

Cause:
The specified file cannot be deleted.

Action:
The file is probably being used by another application. Close that application and try again.

REP-50140
An internal error {0} occurred.

Category:
Other

Cause:
An internal error occurred.

Action:
For assistance, contact Oracle Support Services

REP-50141
File {0} cannot be opened.

Category:
Other

Cause:
Oracle Reports cannot open the specified file.

Action:
Check whether the specified file exists.

REP-50142
File {0} cannot be read.

Category:
Other

Cause:
Oracle Reports cannot read the specified file.

Action:
Check read permission for specified file.

REP-50143
The job is submitted successfully.

Category:
Other

Cause:
The job has been submitted successfully.

Action:
No action required.

REP-50145
Duplicate parameter {0} is specified.

Category:
Other

Cause:
The parameter was specified more than once on the command line.

Action:
Remove the duplicate parameters.

REP-50148
A Base64 format error occurred.

Category:
Other

Cause:
An internal error occurred.

Action:
For assistance, contact Oracle Support Services

REP-50149
The parameter value is invalid: {0}.

Category:
Other

Cause:
Bad parameter value specified.

Action:
Refer to the Oracle Reports documentation for the correct syntax for the parameter.

REP-50150
The Reports Server object cannot be accessed.

Category:
Other

Cause:
An incorrect signature or key to access the Reports Server object was provided.

Action:
Verify permission to access the Reports Server, and correct pair of signature keys.

REP-50151
An error occurred while sending the file to the printer: {0} - {1}.

Category:
Other

Cause:
Error while sending file to specified printer due to the stated reason.

Action:
Correct the error and try again.

REP-50152
An error occurred while sending mail: {0}.

Category:
Other

Cause:
Error while sending mail due to stated reason.

Action:
Correct the error and try again.

REP-50153
The mail to list is missing.

Category:
Other

Cause:
Missing TO or DESNAME parameter for mail. These parameters point to the recipient list of the report.

Action:
Add TO or DESNAME to the command line or the URL.

REP-50155
The job status is unknown.

Category:
Other

Cause:
Unknown job status.

Action:
No action required.

REP-50156
The scheduled job has expired.

Category:
Other

Cause:
The scheduled job has run for specified number of times or its expiration time has passed.

Action:
No action required.

REP-50157
An error occurred while sending the file to printer {0}. Exit with error code {1}.

Category:
Other

Cause:
An error occurred while sending the file to the specified printer.

Action:
Check if the printer or printer driver is correctly installed.

REP-50158
Job finished successfully but output is purged from cache.

Category:
Other

Cause:
The job has finished successfully, but the output has been purged manually or by the cache system and is no longer available.

Action:
Rerun the job to regenerate the output.

REP-50159
The report generated successfully but distribution to destinations failed.

Category:
Other

Cause:
The job has executed successfully, but there were some errors during the distribution of the output.

Action:
Check the error for each destination, fix them if possible, and rerun the job.

REP-50160
The report is distributing.

Category:
Other

Cause:
Oracle Reports is distributing the report.

Action:
No action required.

REP-50161
The database connection string {0} is invalid.

Category:
Other

Cause:
The database connection string format is not correct.

Action:
Specify a correct database connection string in the format userid=<username>/<password>@<tnsname>.

REP-50162
The job output is distributing.

Category:
Other

Cause:
Oracle Reports is distributing the job output.

Action:
No action required.

REP-50163
The job output is copying.

Category:
Other

Cause:
Oracle Reports is copying the job output.

Action:
No action required.

REP-50164
The job output is printing.

Category:
Other

Cause:
Oracle Reports is printing the job output.

Action:
No action required.

REP-50165
The job output is mailing.

Category:
Other

Cause:
Oracle Reports is mailing the job output.

Action:
No action required.

REP-50166
The job output is uploading.

Category:
Other

Cause:
Oracle Reports is uploading the job output.

Action:
No action required.

REP-50168
A syntax error occurred in the Reports Server configuration file {0}.

Category:
Configuration

Cause:
A syntax error occurred in the specified Reports Server configuration file.

Action:
Refer to rwserverconf.xsd for the correct syntax for the server configuration file.

REP-50169
The type of the value for attribute {0} is invalid.

Category:
Other

Cause:
The type of the value for the specified attribute in the server configuration file is not valid.

Action:
Refer to rwserverconf.xsd for correct syntax for the attribute.

REP-50170
A syntax error occurred in the Reports Server configuration XSD file {0}.

Category:
Configuration

Cause:
A syntax error occurred in the the server configuration XSD file.

Action:
Use the original rwserverconf.xsd, without any change.

REP-50171
Authentication failed.

Category:
Security

Cause:
Authentication failed.

Action:
Provide the correct authentication information.

REP-50175
File {0} cannot be found.

Category:
Other

Cause:
Oracle Reports cannot find the specified file.

Action:
Check if the file exists on the file system.

REP-50177
The naming service is not available.

Category:
Other

Cause:
The naming server is down.

Action:
Start the naming server.

REP-50180
The naming service failed to shut down.

Category:
Other

Cause:
Oracle Reports could not stop the naming server.

Action:
For assistance, contact Oracle Support Services

REP-50200
OID server cannot connect.

Category:
Other

Cause:
The OID server is probably down.

Action:
Verify that the OID server is up.

REP-50201
The user role cannot be retrieved from the OID server.

Category:
Other

Cause:
The OID server is probably down.

Action:
Verify that the OID server is up. Also check the Reports Server trace file under $ORACLE_HOME/reports/logs/<server>.trc for more information.

REP-50509
Destination ID {0} failed with error {1}.

Category:
Other

Cause:
Distribution to the ID failed with specified error.

Action:
Check the distribution list and correct the error.

REP-50602
Servlet config file {0} cannot be parsed. {1}.

Category:
Other

Cause:
The servlet config file could not be parsed. The XML syntax is incorrect.

Action:
Correct the servlet config file and start the server.

REP-50603
The servlet file cannot be found {0}. {1}.

Category:
Other

Cause:
The rwservlet file is not found.

Action:
Contact the system administrator.

REP-51000
The Reports Server name is not specified.

Category:
Other

Cause:
The Reports Server name is not specified on the command line or in the URL.

Action:
Specify the Reports Server name as follows: server=<server_name>.

REP-51002
Bind to Reports Server {0} failed.

Category:
Other

Cause:
Failed to connect to Reports Server.

Action:
Verify that Reports Server is running and that the Reports Server name is correct.

REP-51004
Get connection object failed.

Category:
Other

Cause:
Failed to get a connection object from the server. This can happen because the server has reached the maximum number of connections allowed, or the client does not have privileges to make a connection to the server.

Action:
Increase the maxConnect attribute of the connection element and verify that the client has connect privileges to the server.

REP-51015
Sending job output to the client failed due to {0}.

Category:
Other

Cause:
Failed to send job output to client.

Action:
Fix the problem related to stated reason and rerun the job.

REP-51017
The user ID is incomplete.

Category:
Other

Cause:
The value specified for the user ID was incomplete.

Action:
Specify correct syntax for the user ID: <username>/<password>@<tnsname>.

REP-51018
Database user authentication is missing.

Category:
Security

Cause:
No database user authentication information was provided.

Action:
Provide valid database user authentication information.

REP-51019
System user authentication is missing.

Category:
Security

Cause:
No system user authentication information was provided.

Action:
Provide valid system user authentication information.

REP-51020
Authentication for both system user and database user does not match.

Category:
Security

Cause:
The system and the database user authentication information was different.

Action:
Provide the same authentication information for the system and database user.

REP-51021
System and database user authentication is missing.

Category:
Security

Cause:
No system user and database user authentication information was provided.

Action:
Provide valid system and database user authentication information.

REP-51024
The client has not been connected to Reports Server.

Category:
Other

Cause:
An internal error occurred. The client has not connected to Reports Server before using the server.

Action:
For assistance, contact Oracle Support Services.

REP-51025
User {0} does not have the privilege to run command {1}.

Category:
Other

Cause:
An attempt to run the indicated command failed due to insufficient privileges.

Action:
Contact the Oracle Reports administrator to request the necessary privileges.

REP-51026
No output is generated for job {0}.

Category:
Other

Cause:
No output was generated for the indicated job.

Action:
Check the report and job definition and rerun the job.

REP-51027
Engine {0} cannot be killed.

Category:
Other

Cause:
An attempt was made to kill an engine in an older version of Reports Server.

Action:
This operation is not supported.

REP-52001
The key map file {0} cannot be read.

Category:
Other

Cause:
Failed to read the Reports key map file.

Action:
Verify that the Reports key map file is in ORACLE_HOME/reports/conf and that it contains valid information.

REP-52002
The key map file {0} cannot be parsed.

Category:
Other

Cause:
The Reports key map file cannot be parsed.

Action:
Verify that the Reports key map file has valid entries.

REP-52003
Read Reports template {0} failed

Category:
Other

Cause:
The Reports Servlet template cannot be read.

Action:
Verify that the Reports Servlet template is in ORACLE_HOME/reports/templates.

REP-52004
The authentication template {0} cannot be read.

Category:
Security

Cause:
Failed to read the Reports Servlet authentication template.

Action:
Verify that the Reports Servlet authentication template is in ORACLE_HOME/reports/templates.

REP-52005
The specified key {0} does not exist in the key map file.

Category:
Other

Cause:
The specified key does not exist in the Reports key map file.

Action:
Verify that the Reports key map file contains the specified key.

REP-52006
The specified URL {0} cannot be decoded.

Category:
Other

Cause:
The specified URL cannot be decoded.

Action:
Verify that the URL is a valid URL.

REP-52007
A Parameter Form format error was encountered.

Category:
Other

Cause:
The submitted Parameter Form has an invalid format.

Action:
Check if the hidden_run_parameters variable in the Parameter Form is null.

REP-52009
No such Web command ({0}).

Category:
Other

Cause:
The Web command passed in from rwservlet is not a valid command.

Action:
Check the help page for rwservlet for a valid Web command.

REP-52010
The specified key map file {0} does not exist.

Category:
Other

Cause:
The specified key map file does not exist.

Action:
Verify that the Reports key map file is in ORACLE_HOME/reports/conf.

REP-52242
The job with job ID {0} cannot be killed.

Category:
Other

Cause:
Insufficient privileges to perform this operation, or a job with the specified jobid does not exist.

Action:
Sufficient privileges are required for this operation. Either log in as administrator or as a user who has sufficient privileges. Specify a valid jobid in the command.

REP-52251
The output of job ID {0} requested on {1} cannot be retrieved.

Category:
Other

Cause:
Insufficient privileges for this operation, or invalid job ID or nonexistent output.

Action:
Sufficient privileges are required for this operation. Check if a valid job ID is provided in the command.

REP-52260
No Oracle Home is specified.

Category:
Other

Cause:
Oracle Home is not defined in the environment.

Action:
Define Oracle Home in the environment. See Configuration chapter in the Publishing Reports to the Web manual for details.

REP-52261
Parameter {0} has an incorrect value {1}.

Category:
Other

Cause:
The specified parameter has an invalid value.

Action:
Provide correct value for the parameter.

REP-52262
Diagnostic output is disabled.

Category:
Other

Cause:
Reports Server is unsecure, the DIAGNOSTIC property is set to NO in rwservlet.properties file, and a valid AUTHID is not specified in command line.

Action:
Specify a valid AUTHID in the command line or contact the system sdministrator.

REP-52265
The specified Web command {0} is not supported.

Category:
Other

Cause:
The web command is not a valid command for this utility.

Action:
Check the Publishing Reports to the Web manual for a list of valid commands for this utility.

REP-52266
The in-process Reports Server {0} failed to start.

Category:
Other

Cause:
There maybe a server with same name already existing in the network.

Action:
Verify that the server is not already started as a stand alone server.

REP-52268
The specified HTML code is not allowed: {0}

Category:
Other

Cause:
HTML tags were specified in the URL command.

Action:
Either remove the HTML tags in the URL and rerun the report, or set ALLOWHTMLTAGS in rwservlet.properties to YES and restart the OC4J container. However, note that any HTML code included as part of the report request URL may lead to a security compromise as it causes certain browsers to execute any script or code in the URL. This property is set to NO by default, disallowing any malicious HTML code to be entered in the URL when running a report.

REP-52274
Invalid valuess passed.

Category:
Other

Cause:
Invalid values passed to the Web Command.

Action:
Refer to the Oracle Reports help for the Web Command arguments.

REP-52275
Invcompatible arguments passed.

Category:
Other

Cause:
Incompatible arguments passed to the Web Command.

Action:
Refer to the Oracle Reports help for the Web Command arguments.

REP-52280
An Oracle OID generic error occurred.

Category:
Other

Cause:
Failed to get resource type or resoruce values from OID.

Action:
Check the Oracle OID configuration.

REP-52281
The connection to Oracle OID using provider URL {0} cannot be established.

Category:
Other

Cause:
An attempt to connect to Oracle OID using given provider URL and user ID failed.

Action:
Check the Reports Servlet configuration file and verify that the provider URL and user ID are correct.

REP-52282
The specified resource type {0} in OID cannot be found.

Category:
Other

Cause:
The specified resource type is not created in OID

Action:
Verify that the resource type has been defined in OID.

REP-52283
The specified resource key {0} in OID cannot be found.

Category:
Other

Cause:
The specified resource key is not created in OID

Action:
Verify that the resource key has been defined in OID.

REP-52284
The create resource URL cannot be retrieved from OID.

Category:
Other

Cause:
The create resource URL is not defined in OID.

Action:
Verify that the create resource URL has been defined in OID.

REP-52285
The user name or subscriber name cannot be found in Logon Server cookie.

Category:
Other

Cause:
User is not logged on to Logon Server.

Action:
Log on to Logon Server.

REP-52286
Parameter SSOCONN requires the Reports Server to be secure and Single Sign-On turned on.

Category:
Other

Cause:
Either the Reports Server is running in non-secure mode, or the SINGLESIGNON parameter in rwservlet.properties is set to NO.

Action:
Verify that the Reports Server is running in secure mode, and the SINGLESIGNON parameter in rwservlet.properties is set to YES.

REP-52287
Parameter SSOCONN and AUTHID cannot be used together.

Category:
Security

Cause:
SSOCONN and AUTHID are both used in the command line. The AUTHID value overwrites the SSO userid, and SSOCONN requires the SSO user ID. Therefore, using the keywords together on the command line causes a conflict.

Action:
Remove either SSOCONN or AUTHID from the command line.

REP-53000
The connection is invalid.

Category:
Other

Cause:
An internal error occurred.

Action:
For assistance, contact Oracle Support Services.

REP-53053
Arguments for the function call are invalid.

Category:
Other

Cause:
Bad arguments for the function call.

Action:
Refer to the Oracle Reports help for the function arguments.

REP-53054
AUTHID is not allowed in the URL.

Category:
Security

Cause:
AUTHID was specified in the URL.

Action:
Either remove AUTHDID in the URL and rerun the report, or set ALLOWAUTHID in rwservlet.properties to YES and restart the OC4J container.

REP-54000
The cache item is not found in the cache system.

Category:
Other

Cause:
The cache item has been deleted manually or by the cache system.

Action:
Submit the request again to rerun the report.

REP-54001
The cache group item is not found in the cache system.

Category:
Other

Cause:
An internal error occurred.

Action:
Submit the request again without use cache. There is no tolerance in the command line or URL.

REP-54002
The cache item is no longer valid.

Category:
Other

Cause:
The cache item might have been cleaned up by the cache system due to resource constraints.

Action:
Submit the request again to rerun the report.

REP-54003
The syntax for the value of the time argument {0} is invalid.

Category:
Other

Cause:
The syntax for the time argument is incorrect.

Action:
Refer to the Oracle Reports documentation for the correct syntax of the time argument.

REP-54004
No cache directory is specified.

Category:
Other

Cause:
There is no cache directory specified in the server configuration file.

Action:
Specify a cache directory in the server configuration file.

REP-54005
The cache directory {0} does not exist.

Category:
Other

Cause:
The specified cache directory does not exist.

Action:
Create a cache directory before starting Reports Server.

REP-54006
The cache directory {0} cannot be created.

Category:
Other

Cause:
Unable to create a cache directory.

Action:
Ensure write permission and enough disk space for the cache directory.

REP-54007
The cacheSize value specified {0} is invalid.

Category:
Other

Cause:
The cacheSize value specified is not valid.

Action:
Correct the cacheSize value in the server config file and start the server.

REP-55005
An engine access violation occurred.

Category:
Other

Cause:
An incorrect key to access the engine object was provided.

Action:
For assistance, contact Oracle Support Services.

REP-55006
An attempt to load {0} failed.

Category:
Other

Cause:
Failed to load the specified dynamic library.

Action:
Verify that the dynamic library exists in PATH on NT or LD_LIBRARY_PATH on UNIX.

REP-55008
The report cannot be created. The command line is: {0}.

Category:
Other

Cause:
An attempt to create a report in the engine specified on the command line failed.

Action:
For assistance, contact Oracle Support Services.

REP-55009
The Report Engine failed to start. Port {0} specified in the server config file may be already in use.

Category:
Ports

Cause:
The ORB port specified in the config file is not available for the Reports Engine.

Action:
Specify a free port.

REP-55010
An incorrect value is specified for the ORBPorts element.

Category:
Other

Cause:
The ORB port specified is not in valid format.

Action:
Specify a proper integer value for the ORBPorts element.

REP-55100
The urlparameter not specified for the job.

Category:
Other

Cause:
The URL to be downloaded is not specified in the command line.

Action:
Specify the URL in the command line using urlparameter.

REP-55101
A timeout occurred in accessing the URL {0}.

Category:
Performance

Cause:
The engine cannot access the URLstream.

Action:
Check if the URL is accessible. If the engine is running behind a firewall, specify the necessary proxy settings in the server configuration file.

REP-55102
An error occurred setting the proxy information.

Category:
Other

Cause:
Proxy settings could not be set.

Action:
Check if the proxy settings file is valid.

REP-55103
API {0} is not applicable to the URL engine.

Category:
Other

Cause:
The API used is not applicable to the URL engine.

Action:
Verify the API used.

REP-55105
The distribution failed. Verify the distribution list.

Category:
Other

Cause:
The distribution file may be invalid.

Action:
Ensure that the XML distribution file conforms to the DTD.

REP-55106
The DESTYPE value is invalid.

Category:
Other

Cause:
The destination type (DESTYPE) value is null.

Action:
Specify a valid destination type (DESTYPE): FILE, PRINTER, MAIL, or CACHE.

REP-56000
Cluster {0} cannot be joined.

Category:
Other

Cause:
The Reports Server cluster was not joined because other Reports Servers could not be found.

Action:
Verify that this machine can see other Reports Servers. Use osfind to check for other Reports Server on the network.

REP-56001
LocationService cannot be found.

Category:
Other

Cause:
Unable to locate VisiBroker's LocationService.

Action:
This should not happen with VisiBroker 4.5. Report this problem to Oracle Support Services.

REP-56003
References for LocationService cannot be resolved.

Category:
Other

Cause:
References for VisiBroker's LocationService could not be resolved.

Action:
This should not happen with VisiBroker 4.5. Report this problem to Oracle Support Services.

REP-56014
The arguments for function call {0} are invalid.

Category:
Other

Cause:
The arguments for the specified function call were invalid.

Action:
Refer to jasmine.idl for the function arguments.

REP-56017
Security violation: access to job output not allowed.

Category:
Security

Cause:
An attempt was made to access job output by a non-owner.

Action:
This is security violation, and should not be attempted.

REP-56022
Engine {0} cannot be launched due to {1}.

Category:
Other

Cause:
The specified engine could not be launched for the stated reason.

Action:
Fix the problem described in the message, and restart Reports Server.

REP-56027
An internal error occurred: Engine registration failed.

Category:
Other

Cause:
An internal error occurred when registering the engine to Reports Server.

Action:
Contact Oracle Support Services if problem persists.

REP-56030
The initial engine number must be between minengine ({0}) and maxengine ({1}).

Category:
Other

Cause:
The value of initEngine is not between the minEngine and maxEngine values specified in the server configuration file.

Action:
Change the value of initEngine, minEngine, or maxEngine so that minEngine <= initEngine <= maxEngine.

REP-56033
Job {0} does not exist.

Category:
Other

Cause:
The requested job does not exist.

Action:
Specify a valid ID of a job that exists in the Reports Server.

REP-56034
A job that is in current or scheduled queue cannot be resubmitted.

Category:
Other

Cause:
An attempt was made to resubmit a job that is in the current or scheduled job queue.

Action:
Kill or cancel the job in the current or scheduled queue, then resubmit it.

REP-56035
Connection object cannot be accessed.

Category:
Other

Cause:
The client did not provide the correct key to access the connection object in Reports Server.

Action:
This should not happen; ensure that the connection attempt is legitimate.

REP-56036
The job has been scheduled successfully.

Category:
Other

Cause:
This is a notification generated when a job has been scheduled successfully.

Action:
This is a job submission status. No action is needed.

REP-56040
Server {0} already exists in the network.

Category:
Other

Cause:
Another Reports Server in the network has the same name.

Action:
Specify a different name for this Reports Server.

REP-56041
Proxy server for the Reports 6i client cannot be started.

Category:
Other

Cause:
A failure occurred when attempting to start the proxy server that is used for the Reports 6i client.

Action:
Verify that the Reports Server name is defined in tnsnames.ora.

REP-56042
This function is not supported.

Category:
Other

Cause:
The invoked function is not supported.

Action:
Do not use this function.

REP-56043
No securityUserid is specified in the server configuration file.

Category:
Configuration

Cause:
The securityUserid property is missing from the security element specification in the server configuration file.

Action:
Add the securityUserid property to the security element in the server configuration file.

REP-56044
Parameter {0} has invalid value {1}.

Category:
Other

Cause:
The specified parameter has an incorrect value.

Action:
Refer to the Oracle Reports documentation for the correct parameter value syntax and type.

REP-56045
No Oracle Home is specified.

Category:
Other

Cause:
No Oracle Home is specified in the Reports Server running environment.

Action:
Verify that the ORACLE_HOME environment variable is set in the environment where Reports Server runs.

REP-56046
No method {0} is defined in class {1}.

Category:
Other

Cause:
No method is defined in the specified Java class.

Action:
Add the method into the Java class.

REP-56048
Engine {0} crashed.

Category:
Other

Cause:
Reports Server detected that the specified engine crashed.

Action:
Reports Server should restart another engine. Report the problem to Oracle Support Services with the testcase that caused the engine crash.

REP-56049
No portalUserid is specified in the server configuration file.

Category:
Configuration

Cause:
The portalUserid property is missing from the destination element for destype=oraclePortal in the server configuration file.

Action:
Add the portalUserid property to the destination element in the server configuration file.

REP-56050
Persistent file {0} in invalid or corrupted.

Category:
Other

Cause:
An attempt to read the Reports Server persistent file failed.

Action:
Delete the Reports Server persistent file <server_name>.dat in ORACLE_HOME/reports/server.

REP-56051
The connection to server {0} failed.

Category:
Other

Cause:
The specified server in the same cluster may be down or not ready.

Action:
Verify that the server is up and ready.

REP-56052
The connection to server {0} is dropped.

Category:
Other

Cause:
The specified server in the same cluster has been shut down.

Action:
This is for information only, no action is needed.

REP-56053
Cluster server {0} has been registered.

Category:
Other

Cause:
The specified server in the same cluster has been registered.

Action:
This is for information only, no action is needed.

REP-56054
A connection to server {0} is established.

Category:
Other

Cause:
The new Reports Server has connected to the specified Reports Server to form a cluster.

Action:
This is for information only, no action is needed.

REP-56055
The max connections allowed ({0}) is exceeded.

Category:
Other

Cause:
There are more concurrent connection attempts than the server is allowed.

Action:
Increase the value of the maxConnect attribute of the connection element in the server configuration file if desired.

REP-56062
The repositoryConn property is missing from jobStatusRepository.

Category:
Other

Cause:
The repositoryConn property is missing from the jobStatusRepository element specification in the server configuration file.

Action:
Add the repositoryConn property to the jobStatusRepository element in the server configuration file.

REP-56066
PL/SQL error {0} occurred when inserting job information into the database.

Category:
Other

Cause:
The indicated PL/SQL error occurred when inserting job information into the database.

Action:
Check the PL/SQL error manual for the appropriate action.

REP-56067
PL/SQL error {0} occurred when removing job information from the database.

Category:
Other

Cause:
The indicated PL/SQL error occurred when removing job information from the database.

Action:
Check the PL/SQL error manual for the appropriate action.

REP-56068
PL/SQL error {0} occurred when cleaning job information from the database.

Category:
Other

Cause:
The indicated PL/SQL error occurred when cleaning information from the database.

Action:
Check the PL/SQL error manual for the appropriate action.

REP-56069
An internal error occurred: No cache item for job {0}.

Category:
Other

Cause:
No cache item associated with the specified job was found.

Action:
Resubmit the job.

REP-56070
Error message for error {0} cannot be retrieved.

Category:
Other

Cause:
An attempt to retrieve the error message for the specified error code failed.

Action:
Report the problem to Oracle Support Services.

REP-56071
A security check failed with error message {0}.

Category:
Security

Cause:
A security check failed due to the stated reason.

Action:
Verify the privileges to run the report.

REP-56072
The administrator password in the secure server cannot be changed.

Category:
Other

Cause:
An attempt was made to change the Oracle Reports administrator password in secure mode.

Action:
Use Oracle Portal to change the Oracle Reports administrator password.

REP-56073
The password is invalid.

Category:
Other

Cause:
An attempt was made to change the Oracle Reports administrator password, but the old password provided was incorrect.

Action:
Provide the correct old password.

REP-56074
Additional privileges are required to perform the operation.

Category:
Other

Cause:
An attempt was made to perform an operation for which the user does not have privileges.

Action:
Only an Oracle Reports administrator can perform this operation.

REP-56075
The job cannot be reordered if not in the current queue.

Category:
Other

Cause:
An attempt was made to reorder the job in the past or scheduled job queue.

Action:
Reordering jobs can only be done in the current job queue.

REP-56079
The Oracle Portal module status cannot be updated.

Category:
Other

Cause:
An attempt to update the Oracle Portal module status failed.

Action:
Report the problem to Oracle Support Services.

REP-56081
The minEngine value ({0}) must be smaller than maxEngine ({1}).

Category:
Other

Cause:
The value of minEngine is larger than maxEngine in the server configuration file.

Action:
Change the value of minEngine or maxEngine so that minEngine <= maxEngine.

REP-56082
The maxEngine value must be larger than minEngine ({0}) and initEngine ({1}).

Category:
Other

Cause:
The value of maxEngine is smaller than the values of minEngine and initEngine specified in the server configuration file.

Action:
Change the value of initEngine, minEngine, or maxEngine so that minEngine <= initEngine <= maxEngine.

REP-56083
The Oracle Portal folder for job {0} cannot be created.

Category:
Other

Cause:
An attempt to create an Oracle Portal folder for job ouput failed.

Action:
Verify permission to create the folder.

REP-56084
The Oracle Portal folder has been created for job {0}.

Category:
Other

Cause:
This a notification message that the Oracle Portal folder has been created.

Action:
This is for information only, no action is needed.

REP-56085
The engineId {0} is invalid.

Category:
Other

Cause:
An invalid engineId attribute for the job element is specified in the server configuration file.

Action:
Check the engineId attribute in the server configuration file.

REP-56091
Job {0} is redirected to engine {1} on server {2}.

Category:
Other

Cause:
This a notification message that the specified job has been transferred to another server's engine.

Action:
This is for information only, no action is needed.

REP-56092
No class is defined for destination type {0}.

Category:
Other

Cause:
The class attribute is missing for the destination element in the server configuration file.

Action:
Specify the java class name for the destination element in the reports server configuration file.

REP-56093
Cached output for job {0} is no longer valid.

Category:
Other

Cause:
The cached output has been deleted and no longer valid for use.

Action:
Rerun the report.

REP-56095
Job {0} is waiting for the Oracle Portal folder to be created.

Category:
Other

Cause:
This a notification message that the specified job is waiting for the Oracle Portal folder to be created.

Action:
This is for information only, no action is needed.

REP-56096
Registration of the remote server is rejected because it does not participate in the cluster

Category:
Other

Cause:
Another Reports Server tried to register to this Reports Server, but this server does not participate in the cluster.

Action:
This is for information only, no action is needed.

REP-56097
Engine {0} callback timeout is reached.

Category:
Performance

Cause:
The Reports engine callback timeout value was reached.

Action:
Increase the value of the callbackTimeOut attribute for the engine element in the server configuration file.

REP-56098
Engine name {0} is invalid.

Category:
Other

Cause:
The engine name provided to the Reports Server is invalid.

Action:
Report the problem to Oracle Support Services.

REP-56099
The specified jobtype {0} is not supported.

Category:
Other

Cause:
The jobtype provided to the Reports Server is invalid.

Action:
Check the server configuration file to see what jobtypes are supported.

REP-56100
No engine is defined for jobtype {0}.

Category:
Other

Cause:
No engine is defined for specified jobtype in the server configuration file.

Action:
Define an engine for the specified jobtype in the server configuration file.

REP-56101
Reports Server cannot be shut down remotely when running in process mode.

Category:
Process

Cause:
An attempt was made to shut down Reports Server remotely when running in process mode.

Action:
Shut down the process in which Reports Server is running.

REP-56102
The proxy server has terminated unexpectedly.

Category:
Other

Cause:
The proxy server terminated unexpectedly.

Action:
Check whether the Reports Server tnsname is included in tnsnames.ora.

REP-56103
The proxy server callback has timed out.

Category:
Other

Cause:
The proxy server has not called back within an expected time.

Action:
Report the problem to Oracle Support Services.

REP-56104
The pluginParam element {0} is invalid due to {1}.

Category:
Other

Cause:
An invalid value for the pluginParam element is specified in the server configuration file, most likely the file or URL does not exist.

Action:
Verify that the file or URL that is specified for the pluginParam element in the server configuration file is valid.

REP-56105
Engine {0} died with error: {1}.

Category:
Other

Cause:
The specified engine died for the stated reason.

Action:
Fix the error and restart the server.

REP-56106
Engine {0} is destroyed due to timeout.

Category:
Other

Cause:
The specified Engine did not call back in the expected time.

Action:
Increase the value of the callbackTimeOut attribute of the engine element in the server configuration file if desired.

REP-56107
The specified environment ID {0} is invalid for Job Type {1} in the command line.

Category:
Other

Cause:
An invalid ENVID argument is specified in the command line.

Action:
Specify an ENVID that is already defined in the server configuration file (id attribute of environment elelemnt)or define a environment ID in the server configuration file and restart Reports Server.

REP-56108
No connStr property is defined for workflow notification in the server configuration file.

Category:
Configuration

Cause:
The connStr property is not specified for workflow nofication in the server configuration file.

Action:
Specify a valid connStr (in the format of database connection string) for workflow notification in the server configuration file.

REP-56109
Job {0} is terminated due to a connection timeout.

Category:
Other

Cause:
No activity was detected for the specified job in the timeout period. Either the client has terminated unexpectedly, the client program has hung, or the client program took too long handling other processes.

Action:
Check client program status, or if needed, increase the idleTimeOut attribute for connection element in the server configuration file.

REP-56110
The security repository Oracle Portal cannot be connected.

Category:
Security

Cause:
An attempt to connect to Oracle Portal failed. Oracle Portal is probably down, or an invalid connection string was specified.

Action:
Verify that Oracle Portal is up, and the connection string is correct.

REP-56111
Bad or damaged persist file is backed up as: {0}.

Category:
Other

Cause:
Reports Server shut down abnormally while writing to the indicated file.

Action:
Resubmit the lost current and scheduled jobs as information about past, current, and scheduled jobs might be lost. Provide the backed up file when reporting the problem to Oracle Support Services.

REP-56112
Backup of the damaged persist file {0} cannot be created.

Category:
Other

Cause:
The persist file is damaged. Reports Server encountered an error while creating a backup.

Action:
Rename the file manually, then restart Reports Server. Resubmit all current and scheduled jobs as information about past, current, and scheduled jobs will be lost.

REP-56113
The JSP report cannot be resubmitted.

Category:
Other

Cause:
JSP reports are not stored in the Reports Server persistence cache so they cannot be rerun.

Action:
Submit a new JSP report to the Reports Server.

REP-56114
The attempt to bind to the naming server failed.

Category:
Other

Cause:
The naming server may be down.

Action:
Start the naming server.

REP-56115
Engine {0} does not exist.

Category:
Other

Cause:
An attempt was made to access or kill an engine that does not exist.

Action:
Provide the correct engine name.

REP-56116
A relative path for desname {0} is not allowed when destype=file.

Category:
Other

Cause:
A relative path was specified for desname when destype=file, which is not allowed.

Action:
Specify the absolute path for desname.

REP-56117
JOBTYPE {0} is invalid.

Category:
Other

Cause:
An invalid JOBTYPE argument was specified in the command line.

Action:
Correct the JOBTYPE argument and resubmit the job.

REP-56118
The report is aborted upon user request.

Category:
Other

Cause:
This a notification message that the current job was cancelled.

Action:
No action required.

REP-56119
An invalid value {0} is specified for attribute {1}.

Category:
Other

Cause:
The specified value in the server configuration file is invalid for the attribute.

Action:
Refer to the Publishing Reports to the Web manual for information about the attribute and valid values.

REP-56120
A syntax error exists on the command line for the Reports Server.

Category:
Other

Cause:
The syntax for one or more arguments on the command line is invalid.

Action:
Refer to the Publishing Reports to the Web manual for correct command-line argument syntax.

REP-56121
Authentication failed.

Category:
Security

Cause:
The AUTHID specified was invalid.

Action:
Specify a correct AUTHID.

REP-56122
Reports Server {0} cannot be connected.

Category:
Other

Cause:
An attempt to connect to Reports Server failed.

Action:
Verify that Reports Server is running and that the Reports Server name is correct.

REP-56123
An insufficient number of ports is assigned for Reports Server and engines in the config file.

Category:
Ports

Cause:
The number of ports assigned is less than the number required to start server and engines.

Action:
Increase the number of ORB ports in the server configuration file.

REP-56124
Report Server failed to start; port {0} specified in the server config file may already be in use.

Category:
Ports

Cause:
The ORB port specified in the server configuration file is not available for the Reports Server.

Action:
Specify a free port.

REP-56125
The ORBPorts property value in the config file is invalid.

Category:
Other

Cause:
The ORB port specified in the server configuration file is not in a valid format.

Action:
Specify proper integer values for ORB ports either as a range (4000-6000), or comma separated values (4000,5000,6000).

REP-56126
The server config file {0} cannot be parsed. {1}.

Category:
Other

Cause:
An attempt to parse the server config file failed due to invalid XML syntax.

Action:
Correct the server configuration file and start the Reports Server.

REP-56127
The {0} element cannot be decrypted.

Category:
Other

Cause:
An attempt to decrypt the indicated element failed.

Action:
Verify that the encrypted property is set properly for the element in the server configuration file.

REP-56128
The {0} destination cannot be initialized. Nested exception: {1}.

Category:
Other

Cause:
An attempt to initialize the indicated destination failed.

Action:
Check and correct the destination element in the server configuration file.

REP-56129
Permission is denied for {0}.

Category:
Other

Cause:
An attempt to run the report failed due to lack of permissions.

Action:
Change the parameter values or contact the Oracle Reports administrator.

REP-56130
Permission to run Web command {0} is not granted.

Category:
Other

Cause:
An attempt to run the indicated Web command failed due to lack of permissions.

Action:
Contact the Oracle Reports administrator.

REP-56131
Permission to run Web command {0} is not granted.

Category:
Other

Cause:
An attempt to run the indicated Web command failed due to lack of permissions.

Action:
Contact the Oracle Reports administrator.

REP-56132
Access is denied to the report definition file.

Category:
Other

Cause:
An attempt to read the report definition file failed due to lack of permissions.

Action:
Contact the Oracle Reports administrator to obtain access privileges.

REP-56133
Access is denied to write to the specified location.

Category:
Other

Cause:
An attempt to write to the folder failed due to lack of permissions.

Action:
Change the desname location or contact the Oracle Reports administrator.

REP-56134
Server config file cannot be found.

Category:
Other

Cause:
The server configuration file rwserver.conf was not found.

Action:
Contact the Oracle Reports administrator.

REP-56135
Reports Server is not started using PCS.

Category:
Other

Cause:
The Reports Server was not started using PCS in the MAS environment.

Action:
Start the server using PCS.

REP-56136
An error occurred retrieving the environment required to spawn the engine.

Category:
Other

Cause:
An attempt to retrieve needed environment variables failed.

Action:
Contact the Oracle Reports administrator.

REP-56137
The minEngine value must be smaller than maxEngine {0} and initEngine {1}.

Category:
Other

Cause:
The value of minEngine is larger than maxEngine and initEngine in the server configuration file.

Action:
Change the value of initEngine, minEngin, or maxEngine so that minEngine <= initEngine <= maxEngine.

REP-56138
Job {0} has completed execution.

Category:
Other

Cause:
An attempt was made to kill a job that was running or scheduled.

Action:
Check the job status. Only jobs that are running or scheduled can be killed.

REP-56139
The requested operation is unauthorized.

Category:
Other

Cause:
An attempt to perform an operation failed due to lack of proper authorization.

Action:
Contact the Oracle Reports administrator.

REP-57000
An internal error occurred in the Oracle Reports API:

Category:
Other

Cause:
An internal error occurred.

Action:
For assistance, contact Oracle Support Services.

REP-57001
The in-process server is not initialized.

Category:
Other

Cause:
An internal error occurred.

Action:
For assistance, contact Oracle Support Services.

REP-57002
An attempt to load {0} failed.

Category:
Other

Cause:
An internal error occurred.

Action:
For assistance, contact Oracle Support Services.

REP-57003
A column data type {0} is not valid.

Category:
Data

Cause:
A column in the report contains an unsupported data type.

Action:
Use only supported datatypes. Refer to the Oracle Reports documentation for supported datatypes.

REP-57004
The value of column {0} cannot be retrieved, cursor out of range in cache.

Category:
Other

Cause:
An internal error occurred.

Action:
For assistance, contact Oracle Support Services.

REP-57005
The value of column {0} cannot be retrieved in cache.

Category:
Other

Cause:
An internal error occurred.

Action:
For assistance, contact Oracle Support Services.

REP-57052
An internal error occurred in the in-process server.

Category:
Other

Cause:
An internal error occurred.

Action:
For assistance, contact Oracle Support Services.

REP-58000
Attribute value {0} for attribute name {1} in tag {2} is invalid.

Category:
Other

Cause:
The value of the attribute for the JSP tag is invalid.

Action:
Verify that the attribute value is valid. Refer to the Reference>Oracle Reports JSP tags section of the Oracle Reports online Help.

REP-58001
Either tag attribute {0} or {1} must exist in tag {2}.

Category:
Other

Cause:
One of the specified two optional attributes must exist.

Action:
Specify at least one of the two attributes.

REP-58002
A cursor for group {0} cannot be created.

Category:
Other

Cause:
A cursor object cannot be created for a group in an rw:foreach or an rw:graph tag.

Action:
Verify that the group name is valid.

REP-58004
Format trigger {0} cannot be run.

Category:
Other

Cause:
Failed to run a PL/SQL format trigger in an rw:field tag.

Action:
Verify that the name of the format trigger is correct.

REP-58005
There is no current report for group {0}.

Category:
Other

Cause:
There is no report object for the rw:foreach tag.

Action:
Verify that a report object is created by enclosing the report block inside the rw:report tag.

REP-58006
There is no current report for layout object {0}.

Category:
Other

Cause:
There is no report object for the rw:include tag.

Action:
Verify that a report object is created by enclosing the report block inside the rw:report tag.

REP-58008
There is no current report for column {0}.

Category:
Other

Cause:
There is no report object for the rw:field or rw:getValue tags.

Action:
Verify that a report object is created by enclosing the report block inside the rw:report tag.

REP-58009
A cursor containing column {0} cannot be found.

Category:
Other

Cause:
The column does not belong to any of the enclosing cursors.

Action:
Verify that the column name is valid.

REP-58010
Data type {0} is not supported.

Category:
Data

Cause:
Invalid dataType attribute (NOT USED CURRENTLY) in rw:getValue.

Action:
Use any of the supported data types.

REP-58011
ID {0} in {1} tag is used in a previous {2} tag.

Category:
Other

Cause:
The value for the ID attribute is not unique.

Action:
Use a unique ID value.

REP-58012
Only one rw:report tag is allowed in a JSP report.

Category:
Other

Cause:
There is more than one rw:report tag in the JSP report.

Action:
Verify that there is only one rw:report tag in the JSP report.

REP-58013
Only one rw:objects tag is allowed in a JSP report.

Category:
Other

Cause:
More than one rw:objects tags exists in the JSP report.

Action:
Verify that there is only one rw:objects tag in the JSP report.

REP-58014
rw:objects must be the first JSP tag in rw:report body.

Category:
Other

Cause:
A JSP tag other than rw:object is the first Reports JSP tag in the body of the rw:report tag.

Action:
Verify that there is only one rw:objects tag in the body of the rw:report tag. The rw:objects tag must be the first Reports JSP tag inside the body of the rw:report tag.

REP-58015
breakLevel {0} in the rw:field tag does not match the ID of any enclosing rw:foreach.

Category:
Other

Cause:
The value of a breakLevel attribute from an rw:field tag does not match the ID of any enclosing rw:foreach tags.

Action:
Verify that the value for the breakLevel attribute is valid.

REP-58016
The formatMask {0} attribute is not valid.

Category:
Other

Cause:
The value of a formatMask attribute from an rw:field or an rw:getValue tag is invalid.

Action:
Verify that the value for the formatMask attribute is valid.

REP-58017
FormatTrigger {0} in rw:field tag is not a valid PL/SQL program unit.

Category:
Other

Cause:
The value of the formatTrigger attribute from an rw:field tag is not a program unit name, or it has an invalid signature.

Action:
Verify that the value for the formatTrigger attribute is valid.

REP-58018
Column name {0} in {1} of rw:graph is not valid.

Category:
Other

Cause:
A column name specified in one of the attributes of the rw:graph tag is not valid.

Action:
Verify that the column name is valid. Refer to the Reference>Oracle Reports JSP tags section of the Oracle Reports online Help for the correct syntax of the attributes.

REP-58019
Tag {0} (ID {1}) is not in rw:report body.

Category:
Other

Cause:
A Reports JSP tag is not in a rw:report tag's body.

Action:
Add the tag in a rw:report body.

REP-58100
An error occurred starting the internal Web server at port {0}. Error: {1}.

Category:
Ports

Cause:
Errors occurred while starting the internal Web server.

Action:
Verify that the port is not in use. Also check the .log files and log directory under (docroot)/port# for more information. Unless specified from the command line, the docroot should be located at under $REPORTS_TMP/docroot.

REP-58101
An error occurred stopping the internal Web server: {0}.

Category:
Other

Cause:
Errors were encountered while stopping the internal Web server.

Action:
Check the .log files and config directory under (docroot)/port# for more information. Unless specified on the command line, the docroot is located in the $REPORTS_TMP/docroot directory.

REP-58102
An error occurred sending request {0} to the internal Web server: {1}.

Category:
Requests/Responses

Cause:
Errors were encountered when sending the JSP to the internal Web server.

Action:
Check the .log files and the log directory under (docroot)/port# for more information. Unless specified on the command line, the docroot is located in the $REPORTS_TMP/docroot directory.

REP-58103
An error occurred configuring the internal Web server: {0}.

Category:
Other

Cause:
Errors were encountered when configuring the configuration files from the internal Web server.

Action:
Check the .log files and config directory under (docroot)/port# for more information. Unless specified on the command line, the docroot is located in the $REPORTS_TMP/docroot directory.

REP-58104
Port {0} is in use.

Category:
Ports

Cause:
The port specified from the command line is in use.

Action:
Specify a different port, or allow Reports to choose a free port.

REP-58105
A free port within the {0} to {1} range cannot be automatically found for the internal Web server.

Category:
Ports

Cause:
All ports within the range appear to be in use.

Action:
Specify a free port to use from the command line.

REP-58106
Begin port {0} must be less than end port {1}.

Category:
Ports

Cause:
The begin port is greater or equal to end port.

Action:
Specify a begin port less than end port from the command line.

REP-58107
Port numbers must be within range 1-65536.

Category:
Ports

Cause:
The port used is not within the specified range.

Action:
Specify a free port in the specified range from the command line.

REP-58108
HTML tags are not allowed: {0}.

Category:
Other

Cause:
HTML tags were specified in the query string.

Action:
Remove the HTML tags in the query string and rerun the report.

REP-58109
Web server cannot be created.

Category:
Other

Cause:
A problem was encountered while attempting to create the Web server.

Action:
Contact the system administrator.

REP-60003
An error occurred retrieving the environment required to spawn the engine.

Category:
Other

Cause:
Reports Server was unable to retrieve the current environment setting prevailing on the system.

Action:
Ensure that rwu90.dll is installed and available in the system path on Windows. On UNIX, ensure that librwu90.so is installed and available in the LD_LIBRARY_PATH environment variable.

REP-62000
Connection class {0} cannot be loaded.

Category:
Other

Cause:
The connection class mentioned in the configuration file jdbcpds.conf for the selected driver is invalid.

Action:
Ensure that a valid driver connection class is specified in the configuration file jdbcpds.conf and that it is available.

REP-62001
No entry is present for the driver {0} in the jdbcpds.conf file.

Category:
Configuration

Cause:
The driver used in query is not specified in the configuration file jdbcpds.conf.

Action:
Ensure that the entry for the required driver along with the related driver information is specified in the configuration file jdbcpds.conf.

REP-62002
The data source cannot be connected.

Category:
Data

Cause:
The connection information is invalid.

Action:
Ensure that the username, password, database, and driver type are all valid.

REP-62003
Configuration file jdbcpds.conf cannot be found.

Category:
Configuration

Cause:
The configuration file jdbcpds.conf is not found in the reports/conf directory.

Action:
Ensure that the configuration file jdbcpds.conf is available in the reports/conf directory.

REP-62004
A parsing error occurred in the configuration file jdbcpds.conf. Number of errors: {0}

Category:
Configuration

Cause:
The XML section in the configuration file jdbcpds.conf does not conform with its inline DTD.

Action:
Ensure that the XML section in jdbcpds.conf refers to the correct inline DTD.

REP-62005
An error occurred on line number {0}.

Category:
Other

Cause:
An error was found on the specified line of the configuration file jdbcpds.conf.

Action:
Correct the error on the specified line.

REP-62006
The lexical parameter {0} used in the query is invalid.

Category:
Other

Cause:
The lexical parameter used in the query or procedure is invalid.

Action:
Ensure that the query or procedure uses valid lexical parameters. Create new parameters if they are not available.

REP-62007
A SQL error occurred: {0}.

Category:
Other

Cause:
The data source has reported this SQL syntax error in the specified query or procedure.

Action:
Ensure that the syntax of the query or procedure is valid. Refer to the documentation of the specific data source.

REP-62008
The query or procedure for the specified data source is invalid.

Category:
Data

Cause:
The syntax of the query or procedure is invalid for the specified data source.

Action:
Ensure that the syntax of the query or procedure is valid. Refer to the documentation of the specific data source.

REP-62009
The reference parameter value is invalid.

Category:
Other

Cause:
The value of the reference parameter is invalid.

Action:
Verify that the reference column types and values are correct.

REP-62010
A query or procedure is missing.

Category:
Other

Cause:
The query or procedure text field is empty.

Action:
Type a valid query or procedure in the text area.

REP-62011
The database URL {0} is invalid.

Category:
Other

Cause:
Invalid database URL.

Action:
Verify the specified database name and the selected driver type.

REP-62012
Either the number of columns or the types of columns does not match the query definition.

Category:
Other

Cause:
The data fetched does not match the number of columns or the column types that are specified in the query definition.

Action:
Verify that both the number of columns and the column types match the query definition.

REP-62013
The column type {0} used in the query/procedure is not supported by the Reports JDBC query.

Category:
Other

Cause:
This column type is not supported by the Reports JDBC query interface.

Action:
Ensure that only column types that are supported by the Reports JDBC query interface are used. Refer to the JDBC specification and the Reports documentation for supported types.

REP-62014
The inline DTD section of the configuration file jdbcpds.conf has been modified.

Category:
Configuration

Cause:
The format of the inline DTD section in the configuration file jdbcpds.conf has been altered.

Action:
If the DTD format is modified, ensure that the configuration file is valid as per the JDBCPDS requirement.

REP-62015
The sign-on parameter {0} is invalid.

Category:
Other

Cause:
The specified sign-on parameter for the query or procedure is invalid.

Action:
Ensure that the sign-on parameter is available and valid for the JDBC query type in the report.

REP-62016
The sign-on parameter value {0} is invalid.

Category:
Other

Cause:
The specified connect string for this sign-on parameter is invalid.

Action:
Ensure that the specified connect string for this sign-on parameter is valid for the selected driver.

REP-62017
A reference parameter of type Date is not supported by the JDBC driver used.

Category:
Other

Cause:
The driver used to connect to database does not support the Date data type as reference parameter.

Action:
Use the String data type for the reference parameter or use a different JDBC driver that supports the Date data type as reference parameter.

REP-62200
No image exists for the specified ID {0}

Category:
Other

Cause:
The image ID specified does not map to an existing image object in the store.

Action:
For assistance, contact Oracle Support Services.

REP-62201
The image source is invalid

Category:
Other

Cause:
The image source is not valid.

Action:
For assistance, contact Oracle Support Services.

REP-62202
Unsupported image format

Category:
Other

Cause:
The format of the image used is not supported.

Action:
Ensure that the report uses a supported image format as specified in the Oracle Reports documentation.

REP-62203
Internal error reading the image {0}

Category:
Other

Cause:
The image data appears to be corrupt or invalid.

Action:
Ensure that the image is valid. For assistance, contact Oracle Support Services.

REP-62204
Internal error writing the image {0}

Category:
Other

Cause:
There was an internal error writing the image to the output stream.

Action:
For assistance, contact Oracle Support Services.

REP-62205
Internal error during color reduction

Category:
Other

Cause:
An error occurred doing color reduction on GIF images.

Action:
Use a diffent GIF image with lesser colors or chose another image format.

REP-62206
The input image used is corrupt or invalid

Category:
Other

Cause:
The image data appears to be corrupt or invalid.

Action:
Ensure that the image is valid.

REP-62207
Encountered an unsupported version of GIF image

Category:
Other

Cause:
This GIF version is not supported.

Action:
Ensure that the GIF images used adhere to the standards specified in the Oracle Reports documentation.

REP-62350
URL {0} is invalid.

Category:
Other

Cause:
The location pointed to by the URL appears to be invalid.

Action:
Ensure that the location pointed to by the URL is valid.

REP-62351
The proxy setting specified in proxyinfo.xml will be not be effective.

Category:
Other

Cause:
The proxy setting was ignored due to an invalid configuration in the proxyinfo.xml file.

Action:
Ensure that the proxy setting in proxyinfo.xml is correct.

REP-62352
The FTP proxy server specified is not responding : {0}.

Category:
Other

Cause:
The proxy specified in the proxyinfo.xml file does not support SOCKS protocol.

Action:
Ensure that the proxy supports SOCKS protocol.

REP-62353
The destination file name is missing.

Category:
Other

Cause:
Destination file name missing in the desname argument.

Action:
Specify a valid destination file name.

REP-62354
The directory specified is invalid.

Category:
Other

Cause:
Invalid directory is specified in the desname argument.

Action:
Specify a valid directory path.

REP-62370
URL {0} is invalid.

Category:
Other

Cause:
The location pointed to by the URL appears to be invalid.

Action:
Ensure that the location pointed by the URL is valid.

REP-62371
The proxy setting specified in proxyinfo.xml is not be effective.

Category:
Other

Cause:
The proxy setting was ignored due to an invalid configuration in the proxyinfo.xml file.

Action:
Ensure that the proxy setting in proxyinfo.xml is correct.

REP-63000
No URL specified for {0}

Category:
Other

Cause:
There was no URL specified for either the data definition or the data source.

Action:
Specify a URL for both the data definition and the data source.

REP-63001
Invalid stream in the Data Definition URL {0}

Category:
Data

Cause:
The Data Stream pointed to by the URL appears to be invalid.

Action:
Ensure that the XML Stream pointed to by the URL is valid.

REP-63002
URL specified has an invalid XML stream: {0}

Category:
Other

Cause:
The URL appears to have invalid XML stream.

Action:
Ensure that the XML stream pointed to by the URL contains valid XML.

REP-63003
URL {0} read error

Category:
Other

Cause:
Could not access the specified URL. A timeout occurred while accessing the URL.

Action:
Ensure that the URL is accessible and check that the proxy information in the xmlpds.conf file is correct.

REP-63004
Generic error while parsing the URL stream {0}

Category:
Other

Cause:
The data stream pointed to by the URL appears to be invalid.

Action:
Ensure that the XML stream pointed to by the URL is valid.

REP-63005
The Inline DTD section of xmlpds.conf file has been modified

Category:
Configuration

Cause:
The Inline DTD section of the configuration file xmlpds.conf has been modified.

Action:
Ensure that the configuration file is still valid, per the XMLPDS requirement.

REP-63006
Invalid reference parameter value

Category:
Other

Cause:
The value of the reference parameter is invalid.

Action:
Verify that the types and values of the referenced columns are correct.

REP-63007
Configuration file xmlpds.conf not found

Category:
Configuration

Cause:
The configuration file xmlpds.conf was not found in the reports/conf directory.

Action:
Ensure that the configuration file xmlpds.conf is located in the reports/conf directory.

REP-63008
Parsing error in the xmlpds.conf configuration file Number of errors: {0}

Category:
Configuration

Cause:
The XML section in the xmlpds.conf file does not conform with the corresponding inline DTD.

Action:
Ensure the XML section in the xmlpds.conf file conforms with the corresponding inline DTD.

REP-63009
The proxy setting specified in xmlpds.conf will be not be effective

Category:
Configuration

Cause:
The proxy setting was ignored due to an invalid configuration in the xmlpds.conf file.

Action:
Ensure that the proxy setting in the configuration file xmlpds.conf is correctly specified.

REP-63500
No URL is specified for data source {0}/

Category:
Data

Cause:
There was no URL specified for the data source.

Action:
Specify a URL for the data source.

REP-63501
The specified URL {0} is not compatible with the file format {1} at line number {2}.

Category:
Other

Cause:
The URL appears to have invalid content.

Action:
Ensure that the content pointed to by the URL is a valid file format.

REP-63502
The data is invalid.

Category:
Data

Cause:
Content is not compatible with the file format selected.

Action:
Ensure that the text is valid for the file format selected.

REP-63503
Either the number of columns or the type of columns does not match the query definition.

Category:
Other

Cause:
The data fetched does not match the number of columns or the column types that are specified in the query definition.

Action:
Verify that both the number of columns and the column types match the query definition.

REP-63504
A read error occurred in accessing URL {0}.

Category:
Other

Cause:
Could not access the specified URL. A timeout occurred while accessing the URL.

Action:
Ensure that the URL is accessible and check that the proxy information in the textpds.conf file is correct.

REP-63505
The Inline DTD section of textpds.conf has been modified.

Category:
Configuration

Cause:
The Inline DTD section of the configuration file textpds.conf has been modified.

Action:
Ensure that the configuration file is still valid, per the TextPDS requirement.

REP-63506
The reference parameter is invalid.

Category:
Other

Cause:
The reference parameter is invalid.

Action:
Verify that the name, types, and values of the referenced columns are correct.

REP-63507
The configuration file textpds.conf cannot be found.

Category:
Configuration

Cause:
The configuration file textpds.conf was not found in the reports/conf directory.

Action:
Ensure that the configuration file textpds.conf is located in the reports/conf directory.

REP-63508
A parsing error occurred in textpds.conf. Number of errors: {0}.

Category:
Other

Cause:
The XML section in the textpds.conf file does not conform with the corresponding inline DTD.

Action:
Ensure the XML section in the textpds.conf file conforms with the corresponding inline DTD.

REP-63509
The proxy setting specified in textpds.conf is invalid.

Category:
Configuration

Cause:
The proxy setting was ignored due to an invalid configuration in the textpds.conf file.

Action:
Ensure that the proxy setting in the configuration file textpds.conf is correctly specified.

REP-63510
No fileFormat is specified in textpds.conf.

Category:
Other

Cause:
The entry for fileFormat in textpds.conf is missing.

Action:
Ensure that at least one fileFormat element is specified in the textpds.conf.

REP-63511
The fileFormat specification is invalid.

Category:
Other

Cause:
The entry for fileFormat in textpds.conf is invalid.

Action:
Ensure that fileFormat is specified per the DTD of textpds.conf.

REP-63512
No entry is present for fileFormat {0} in textpds.conf.

Category:
Other

Cause:
The fileFormat used in the query is not defined in textpds.conf.

Action:
Ensure that the entry for the required fileFormat along with the column information is specified in textpds.conf.

REP-63513
The Serialized XML section of the saved report is invalid.

Category:
Other

Cause:
The Serialized XML section has been modified.

Action:
Ensure that Serialized XML section is specified per the TextPDS format.

REP-63514
The column type {0} used in the query is not supported by a Text query.

Category:
Other

Cause:
This column type is not supported by the Text query interface.

Action:
Ensure that only column types that are supported by the Text query interface are used. Refer to the TextPDS specification and the Oracle Reports documentation for supported types.

REP-63515
The data in log file {0} is not according to the date pattern {1} specified in the config file.

Category:
Data

Cause:
The data in the log file is not valid according to the date pattern specified in the config file.

Action:
Ensure that data in the log file is specified according to the date pattern.

REP-64000
No Oracle Home is specified.

Category:
Other

Cause:
ORACLE_HOME is missing in the command line.

Action:
Specify ORACLE_HOME=<oracle_home_dir> in the command line.

REP-64001
The Oracle Reports Bridge failed to start.

Category:
Other

Cause:
The Oracle Reports Bridge failed to start.

Action:
Check log file for detailed message and take appropriate action.

REP-64002
The Oracle Reports Bridge initialization failed {0}.

Category:
Other

Cause:
The Oracle Reports Bridge initialization failed.

Action:
Check the actual message and take appropriate action.

REP-64003
The local port is not set. One-way Oracle Reports Bridge is started.

Category:
Ports

Cause:
One-way Oracle Reports Bridge is started.

Action:
No action needed. Set local port to start two-way bridge if needed.

REP-64004
AUTHID is not specified.

Category:
Security

Cause:
AUTHID argument is not specified in command line.

Action:
Specify AUTHID=<username>/<password> in the command line.

REP-64005
Authentication failed.

Category:
Security

Cause:
The AUTHID specified was invalid.

Action:
Specify a correct AUTHID.

REP-64006
The Oracle Reports Bridge shutdown failed.

Category:
Other

Cause:
An attempt to shut down The Oracle Reports Bridge failed.

Action:
Check the trace for detailed message and take appropriate action.

REP-64009
The Oracle Reports Bridge is already running.

Category:
Other

Cause:
Another Oracle Reports Bridge is already running with the same port.

Action:
Change the port in the config file and start again.

REP-64010
The local listener failed to start.

Category:
Other

Cause:
The open socket could not be opened.

Action:
Check socket is available and usable.

REP-64011
Request {0} cannot be served.

Category:
Requests/Responses

Cause:
Unable to serve the Oracle Reports Bridge request.

Action:
Check the actual message and take appropriate action.

REP-64012
A fatal error {0} occurred. Restart the Oracle Reports Bridge.

Category:
Other

Cause:
The Oracle Reports Bridge is not able to serve any request.

Action:
Restart the Oracle Reports Bridge.

REP-64013
The Oracle Reports Bridge failed to serve the request {0}.

Category:
Requests/Responses

Cause:
An internal error occurred.

Action:
Check the actual message; the Oracle Reports Bridge may recover from this error.

REP-64014
The Oracle Reports Bridge name is not specified.

Category:
Other

Cause:
The NAME=<bridgename> argument is missing in the command line.

Action:
Specify NAME=<bridgename> in the command line.

REP-64015
The command is invalid.

Category:
Other

Cause:
Invalid command-line argument.

Action:
Check command-line arguments.

REP-64016
Cannot connect to the Oracle Reports Bridge {0}.

Category:
Other

Cause:
The Oracle Reports Bridge is not running on specified port.

Action:
The Oracle Reports Bridge may be down. Or check the Bridge port in Bridge config file and try again.

REP-64017
The Oracle Reports Bridge config file is not found.

Category:
Other

Cause:
Configuration file rwbridge.conf is not found.

Action:
Contact the Oracle Reports administrator.

REP-64018
The Oracle Reports Bridge is not started using PCS.

Category:
Other

Cause:
The Oracle Reports Bridge is not started using PCS in the MAS environment.

Action:
Start the Oracle Reports Bridge using PCS.

REP-65001
Communication error {0} occurred.

Category:
Other

Cause:
A network IO error occurred.

Action:
Check the actual message and take appropriate action.

REP-65002
The communication channel {0} cannot be initialized.

Category:
Other

Cause:
Multicast initialization failed.

Action:
Check the actual message and take appropriate action.

REP-65003
The request timed out.

Category:
Requests/Responses

Cause:
Waiting for a response from the server timed out.

Action:
No action required. If all retries fail, increase the timeout value in the network config file.

REP-65004
The naming server cannot be bound.

Category:
Other

Cause:
Naming service may be down.

Action:
Start the naming service and try again.

REP-65005
The network config file cannot be found.

Category:
Network

Cause:
rwnetwork.conf is not found.

Action:
Contact the Oracle Reports administrator.

REP-67000
Creation of Reports Server instance {0} on machine {1} failed

Category:
Other

Cause:
Attempt to create reports server instance failed

Action:
Check the actual error message and take appropriate action

REP-67001
Removal of Reports Server instance {0} failed

Category:
Other

Cause:
Attempt to remove reports server instance failed

Action:
Check the actual error message and take appropriate action

REP-67002
Unable to register reports server configuration mbeans

Category:
Other

Cause:
Reports server configuration mbeans registration failed

Action:
For assistance, contact Oracle Support Services

REP-67004
Validation of component failed: {0}

Category:
Other

Cause:
Component is not successfully validated for attempted operation

Action:
Check the actual error message and take appropriate action

REP-67100
Unable to calculate checksum of file {0}

Category:
Other

Cause:
Checksum calculation of file failed

Action:
For assistance, contact Oracle Support Services

REP-67101
Error in replicating reports server configuration

Category:
Other

Cause:
Replication of configuration from AdminServer machine to managed server failed

Action:
For assistance, contact Oracle Support Services

REP-67200
Creation of Reports Tools instance {0} on machine {1} failed

Category:
Other

Cause:
Attempt to create reports tools instance failed

Action:
Check the actual error message and take appropriate action

REP-67201
Removal of Reports Tools instance {0} failed

Category:
Other

Cause:
Attempt to remove reports tools instance failed

Action:
Check the actual error message and take appropriate action

REP-67202
Unable to register reports tools configuration mbeans

Category:
Other

Cause:
Reports tools configuration mbeans registration failed

Action:
For assistance, contact Oracle Support Services

REP-67204
Validation of component failed: {0}

Category:
Other

Cause:
Component is not successfully validated for attempted operation

Action:
Check the actual error message and take appropriate action

REP-67300
Unable to calculate checksum of file {0}

Category:
Other

Cause:
Checksum calculation of file failed

Action:
For assistance, contact Oracle Support Services

REP-67301
Error in replicating reports tools configuration

Category:
Other

Cause:
Replication of configuration from AdminServer machine to managed server failed

Action:
For assistance, contact Oracle Support Services

REP-67400
Creation of Reports Bridge instance {0} on machine {1} failed

Category:
Other

Cause:
Attempt to create reports bridge instance failed

Action:
Check the actual error message and take appropriate action

REP-67401
Removal of Reports Bridge instance {0} failed

Category:
Other

Cause:
Attempt to remove reports bridge instance failed

Action:
Check the actual error message and take appropriate action

REP-67402
Unable to register reports bridge configuration mbeans

Category:
Other

Cause:
Reports bridge configuration mbeans registration failed

Action:
For assistance, contact Oracle Support Services

REP-67404
Validation of component failed: {0}

Category:
Other

Cause:
Component is not successfully validated for attempted operation

Action:
Check the actual error message and take appropriate action

REP-67500
Unable to calculate checksum of file {0}

Category:
Other

Cause:
Checksum calculation of file failed

Action:
For assistance, contact Oracle Support Services

REP-67501
Error in replicating reports bridge configuration

Category:
Other

Cause:
Replication of configuration from AdminServer machine to managed server failed

Action:
For assistance, contact Oracle Support Services

REP-67550
Component {0} already exists in domain

Category:
Other

Cause:
Component with given name already exists in domain

Action:
Provide a unique component name

REP-67551
Component {0} cannot be removed because it is in state {1}

Category:
Other

Cause:
Component is not in following states : SHUTDOWN, FAILED_NOT_RESTARTABLE, FAILED

Action:
Shutdown the component

REP-67552
Component is not configured to OID

Category:
Other

Cause:
Component is not associated to OID

Action:
Associate component to OID

REP-67600
Connect to a WebLogic server before using this command

Category:
Other

Cause:
Not connected to Weblogic server

Action:
Connect to Weblogic server using appropriate WLST command

REP-67601
createReportsServerInstance command failed

Category:
Other

Cause:
Attempt to create reports server instance failed

Action:
Check the actual error message and take appropriate action

REP-67602
deleteReportsServerInstance command failed

Category:
Other

Cause:
Attempt to remove reports server instance failed

Action:
Check the actual error message and take appropriate action

REP-67603
Argument {0} is not valid

Category:
Other

Cause:
Invalid argument provided to WLST command

Action:
Provide correct argument to WLST command

REP-67604
The following required arguments are missing :{0}

Category:
Other

Cause:
Required argument not provided to WLST command

Action:
Provide required argument to WLST command

REP-67608
associateStandaloneServer command failed

Category:
Other

Cause:
Association of reports server to OID failed

Action:
Check the actual error message and take appropriate action

REP-67610
dissociateStandaloneServer command failed

Category:
Other

Cause:
Dissociation of reports server from OID failed

Action:
Check the actual error message and take appropriate action

REP-67612
associateInprocessServer command failed

Category:
Other

Cause:
Association of reports server to OID failed

Action:
Check the actual error message and take appropriate action

REP-67614
dissociateInprocessServer command failed

Category:
Other

Cause:
Dissociation of reports server from OID failed

Action:
Check the actual error message and take appropriate action

REP-67700
Connect to a WebLogic server before using this command

Category:
Other

Cause:
Not connected to Weblogic server

Action:
Connect to Weblogic server using appropriate WLST command

REP-67701
createReportsToolsInstance() failed

Category:
Other

Cause:
Attempt to create reports tools instance failed

Action:
Check the actual error message and take appropriate action

REP-67702
deleteReportsToolsInstance() failed

Category:
Other

Cause:
Attempt to remove reports tools instance failed

Action:
Check the actual error message and take appropriate action

REP-67703
Argument {0} is not valid

Category:
Other

Cause:
Invalid argument provided to WLST command

Action:
Provide correct argument to WLST command

REP-67704
The following required arguments are missing :{0}

Category:
Other

Cause:
Required argument not provided to WLST command

Action:
Provide required argument to WLST command

REP-67800
Connect to a WebLogic server before using this command

Category:
Other

Cause:
Not connected to Weblogic server

Action:
Connect to Weblogic server using appropriate WLST command

REP-67801
createReportsBridgeInstance() failed

Category:
Other

Cause:
Attempt to create reports bridge instance failed

Action:
Check the actual error message and take appropriate action

REP-67802
deleteReportsBridgeInstance() failed

Category:
Other

Cause:
Attempt to remove reports bridge instance failed

Action:
Check the actual error message and take appropriate action

REP-67803
Argument {0} is not valid

Category:
Other

Cause:
Invalid argument provided to WLST command

Action:
Provide correct argument to WLST command

REP-67804
The following required arguments are missing :{0}

Category:
Other

Cause:
Required argument not provided to WLST command

Action:
Provide required argument to WLST command

REP-67900
Reports 12c Application not found deployed for managed server {0}

Category:
Other

Cause:
Reports 12c Application not found deployed for managed server

Action:
Start reports managed servers once so that reports 12c applications get automatically deployed. Then shutdown managed servers.

REP-67901
Component of type {0} and name {1} does not exist in 12c domain

Category:
Other

Cause:
Reports system component not found in 12c domain

Action:
Use WLST command to create reports component in 12c domain

REP-67902
Config file not found : {0}

Category:
Other

Cause:

Action:
Reports installation is corrupted

REP-67903
Topology document parsing error

Category:
Other

Cause:

Action:
Reports 11g domain is corrupted

REP-67904
Topology document not found : {0}

Category:
Other

Cause:
Reports 11g domain is corrupted or is already upgraded

Action:
Contact the system administrator

REP-80001
An internal error occurred.

Category:
Other

Cause:
Unexpected internal exception.

Action:
For assistance, contact Oracle Support Services.

REP-80002
The report object is invalid.

Category:
Other

Cause:
The report object is invalid, possibly invalid object handle, or an already deleted object.

Action:
Discard this object handle and get a new one.

REP-80003
The report object name is invalid.

Category:
Other

Cause:
The name does not follow report object naming rules; for example, it may contain an invalid character.

Action:
Follow the report object naming rules to create a valid name.

REP-80004
A dialog window not allowed at this time.

Category:
Other

Cause:
The Plugin tried to display a dialog window when it is not allowed; for example, when Reports is running in batch mode.

Action:
Plugin must not raise a dialog window when it is not allowed.

REP-80005
The dialog window location is invalid.

Category:
Other

Cause:
The requested dialog window location is invalid.

Action:
Set a valid dialog window location.

REP-80006
The dialog window size is invalid.

Category:
Other

Cause:
The requested dialog window size is invalid.

Action:
Set a valid dialog window size.

REP-80007
The help system cannot be displayed.

Category:
Other

Cause:
Failure to display online help.

Action:
Check the online help system setup.

REP-80008
The helpset ID is invalid.

Category:
Other

Cause:
Invalid helpset ID.

Action:
Correct the helpset ID.

REP-80009
The help topic is invalid.

Category:
Other

Cause:
The help topic is invalid.

Action:
Correct the help topic.

REP-80010
The trace file cannot be written to.

Category:
Other

Cause:
Fail to write to trace file.

Action:
Check the trace file setup, file write permission, and whether the disk is full.

REP-80011
Sign-on parameter {0} for {1} cannot be set.

Category:
Other

Cause:
The column is not a valid sign-on parameter of this plugin type.

Action:
Use the Property Palette to set this column as a sign-on parameter of this plugin type.

REP-80012
The link between two columns of mismatched datatypes is invalid.

Category:
Other

Cause:
The column link is formed between two columns of different data types.

Action:
Ensure the link is formed between the columns whose datatypes are compatible.

29

SDP-26500 to SDP-26236

SDP-26500
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26501
Failed to deliver a message to the gateway at {0}. No Status could be generated for the failed message.

Category:
Process

Cause:
A message failed to be delivered to the gateway.

Action:
Check the connectivity to the gateway

SDP-26502
Unable to connect to the Feedback service at {0}. Will retry to connect.

Category:
Process

Cause:
Unable to poll the Feedback service, due to a network problem.

Action:
Check the connectivity to the Feedback service.

SDP-26503
Unable to poll the Feedback service at {0}.

Category:
Process

Cause:
Unable to poll the Feedback service, probably due to a network problem.

Action:
Check the connectivity to the Feedback service.

SDP-25001
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25002
Unable to create JNDI Context.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details. Check the JNDI Context initialization parameters.

SDP-25003
Unable to create an instance of Driver Locator.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25004
Message could not be delivered to client due to rollback at the client application. Message ID {0}.

Category:
Process

Cause:
The client did rollback on the transaction, hence the message could not be re-delivered to the client.

Action:
Check why the client did rollback

SDP-25005
Failed to create Sending Core instance.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25006
Failed to remove an EJB instance.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25007
An error occurred while processing an outbound message.

Category:
Process

Cause:
The outbound JMS message does not contain a valid message or request information.

Action:
Check the stack trace for more details.

SDP-25008
An error occurred while processing an outbound message.

Category:
Process

Cause:
An exception has occurred while processing the outbound message.

Action:
Check the stack trace for more details.

SDP-25009
An error occurred while storing a message.

Category:
Process

Cause:
An exception has occurred while processing the message.

Action:
Check the stack trace for more details.

SDP-25010
An error occurred while sending an outbound message.

Category:
Process

Cause:
An exception has occurred while processing the outbound message.

Action:
Check the stack trace for more details.

SDP-25011
An error occurred while transforming an outbound message.

Category:
Process

Cause:
An exception has occurred while processing the outbound message.

Action:
Check the stack trace for more details.

SDP-25012
An error occurred while processing error statuses.

Category:
Process

Cause:
An exception has occurred while processing error statuses.

Action:
Check the stack trace for more details.

SDP-25013
An error occurred while resending an outbound message.

Category:
Process

Cause:
An exception has occurred while processing the resent outbound message.

Action:
Check the stack trace for more details.

SDP-25014
A JMS exception occurred, trying to recover

Category:
Process

Cause:
A JMS exception occurred

Action:
Check the stack trace for more details.

SDP-25015
There are no transformed messages of message {0} for recipients {1}. Skipping message delivery to these recipients.

Category:
Process

Cause:
An error has occurred while transforming an outbound message.

Action:
Use the messageId to trace the message handling.

SDP-25016
Could not get TimerService or Timers.

Category:
Process

Cause:
Could not get TimerService or Timers.

Action:
Check application server status.

SDP-25017
Could not cancel timer.

Category:
Process

Cause:
Could not cancel timer

Action:
Check the stack trace for more details.

SDP-25020
Unable to schedule a timed failover event.

Category:
Process

Cause:
An exception has occurred while scheduling a timed failover event.

Action:
Check the stack trace for more details.

SDP-25021
An error occurred while processing a timed failover event.

Category:
Process

Cause:
An exception has occurred while processing a timed failover event.

Action:
Check the stack trace for more details.

SDP-25022
Unable to schedule a timed resend event.

Category:
Process

Cause:
An exception has occurred while scheduling a timed resend event.

Action:
Check the stack trace for more details.

SDP-25030
Unable to schedule a timer to refresh the driver locator cache.

Category:
Process

Cause:
An exception has occurred while scheduling a timer to refresh the driver cache.

Action:
Check the stack trace for more details.

SDP-25032
An error occurred while registering driver information {0}.

Category:
Process

Cause:
An exception has occurred while registering the driver information.

Action:
Check the stack trace for more details.

SDP-25033
An error occurred while unregistering driver information {0}.

Category:
Process

Cause:
An exception has occurred while unregistering the driver information.

Action:
Check the stack trace for more details.

SDP-25034
There are total {0} registered User Messaging Drivers. Driver(s): {1}.

Category:
Process

Cause:
A Messaging Driver registered with the Messaging Server

Action:
None

SDP-25035
Messaging store not found.

Category:
Process

Cause:
An exception has occurred while attempting to find the messaging store.

Action:
Check the stack trace for more details.

SDP-25036
An error occurred while registering driver information at User preference subsystem {0}.

Category:
Process

Cause:
An exception has occurred while registering the driver information at User preference subsystem.

Action:
Check the stack trace for more details.

SDP-25037
An error occurred while unregistering driver information at User preference subsystem {0}.

Category:
Process

Cause:
An exception has occurred while unregistering the driver information at User preference subsystem.

Action:
Check the stack trace for more details.

SDP-25040
Unable to create an instance of CommandReceiverBean.

Category:
Process

Cause:
An exception has occurred while attempting to process a command.

Action:
Check the stack trace for more details.

SDP-25042
An error occurred while processing a command message.

Category:
Process

Cause:
An exception has occurred while attempting to process a command.

Action:
Check the stack trace for more details.

SDP-25043
An unknown command message was received, ignoring: {0}.

Category:
Process

Cause:
The engine received an unknown command message and was unable to process the command.

Action:
Check the current log file for additional details, if the system is not functional. Otherwise, ignore this warning.

SDP-25055
Failed to create Receiving Core instance.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25057
An error occurred while processing an inbound JMS message.

Category:
Process

Cause:
The inbound JMS message does not contain a valid message.

Action:
Check the stack trace for more details.

SDP-25058
An error occurred while processing an inbound message.

Category:
Process

Cause:
An exception has occurred while processing the inbound message.

Action:
Check the stack trace for more details.

SDP-25059
An unknown JMS message is received, ignoring: {0}.

Category:
Process

Cause:
The engine received an unknown JMS message and was unable to process it.

Action:
Check the current log file for additional details, if the system is not functional. Otherwise, ignore this warning.

SDP-25060
There is no application that has registered this address as an access point. The message will be delivered when the access point is registered. Address={0}

Category:
Process

Cause:
There is no application that has registered this recipient address as an access point.

Action:
Register the access point. The message is kept in a pending queue until an application registers a corresponding access point.

SDP-25061
An error occurred while processing inbound message statuses.

Category:
Process

Cause:
An exception has occurred while attempting to process inbound message statuses.

Action:
Check the stack trace for more details.

SDP-25063
Status not delivered to client since no client information found for application {0}.

Category:
Process

Cause:
There is no application client information stored.

Action:
Check the log file for additional information.

SDP-25064
An error occurred while recording a status processing update.

Category:
Process

Cause:
An exception has occurred while attempting to record a status processing update.

Action:
Check the stack trace for more details.

SDP-25065
An error occurred while sending a message to failover address {0}.

Category:
Process

Cause:
An exception has occurred while sending out a failover message.

Action:
Check the stack trace for more details.

SDP-25066
An error occurred while processing an outbound message status.

Category:
Process

Cause:
An exception has occurred while attempting to process an outbound message status.

Action:
Check the stack trace for more details.

SDP-25070
Unable to retrieve messaging engine sending and/or receiving queues from configuration.

Category:
Process

Cause:
A severe configuration error has occurred and the system is not functional.

Action:
Check the messaging engine configuration and the stack trace, if available, for more details.

SDP-25081
An error occurred while adding a message converter rule: {0}.

Category:
Process

Cause:
An invalid message converter rule was provided.

Action:
Check the log file for additional details.

SDP-25082
No predicates and/or devices matched. Ignoring converter rule (MIME type: {0}, delivery type: {1}, predicate: {2}).

Category:
Process

Cause:
An invalid message converter rule was provided.

Action:
Check the log file for additional details.

SDP-25083
Message content is not an instance of MimeMultipart.

Category:
Process

Cause:
An invalid message content was provided to this converter.

Action:
Check the current log file for additional details. Check User Messaging Service Javadoc on OTN for more information on sending MimeMultipart messages.

SDP-25085
Message {0} has a nonunique Message ID or recipient, and does not look like a redelivery attempt.

Category:
Process

Cause:
A message was sent or received that appears to be a duplicate of an already processed message; re-enqueuing message with delay specified.

Action:
Ensure that messages are assigned unique Message IDs.

SDP-25087
No matching driver found for {0} = {1}.

Category:
Process

Cause:
No matching driver found for the given property.

Action:
Check that there is a correctly deployed and configured driver matching the given property.

SDP-25088
Unable to refresh the driver locator cache, due to exception.

Category:
Process

Cause:
An error has occurred while refreshing the driver locator cache.

Action:
Check the reported error message and correct any configuration problems.

SDP-25089
Status could not be delivered to client due to rollback at the client application. Message ID {0} {1}.

Category:
Process

Cause:
The client did rollback on the transaction, hence the status could not be re-delivered to the client.

Action:
Check why the client did rollback

SDP-25101
Caught a database exception.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25106
Conflicting recipient IDs for Message {0}.

Category:
Process

Cause:
A conflict between recipient identifiers has been detected.

Action:
Ensure that applications are using unique Message IDs.

SDP-25107
Message ID {0} in Status object does not match previously recorded Message ID {1}.

Category:
Process

Cause:
A status object returned from a driver contained a different Message ID than expected.

Action:
Ensure that drivers are mapping Gateway IDs to Message IDs correctly.

SDP-25109
Failed to initialize persistence context.

Category:
Process

Cause:
An exception has occurred while initializing the persistence context.

Action:
Check the stack trace for more details.

SDP-25202
Parameter {0} is missing in SOAPMessageContext sent from client. Generating default value.

Category:
Process

Cause:
The client application sent a message without required attribute.

Action:
Make sure the client application add ApplicationName, ApplicationInstanceName, and ClientType to the SOAPMessageContext.

SDP-25250
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25251
Messaging Exception while processing Parlay X request.

Category:
Process

Cause:
A Messaging Exception has occurred.

Action:
Check the stack trace for more details.

SDP-25252
Exception while initializing Parlay X Messaging servlet.

Category:
Process

Cause:
An exception occurred while initializing the Parlay X Messaging servlet.

Action:
Check the stack trace for more details.

SDP-25253
Exception while initializing Parlay X Messaging content servlet.

Category:
Process

Cause:
An exception occurred while initializing the Parlay X Messaging content servlet.

Action:
Check the stack trace for more details.

SDP-25254
Exception while processing SOAP attachment content.

Category:
Process

Cause:
An exception occurred while processing message content in a SOAP attachment.

Action:
Check the stack trace for more details.

SDP-25255
Message contains multiple attachments. All but first attachment will be ignored.

Category:
Process

Cause:
The client application sent a message with multiple attachment parts.

Action:
Client applications should send one attachment part per message. Complex content should be sent as a MIME Multipart object.

SDP-25256
Parameter {0} is missing in SOAPMessageContext sent from client. Generating default value.

Category:
Process

Cause:
The client application sent a message without required attribute.

Action:
Make sure the client application add ApplicationName, ApplicationInstanceName, and ClientType to the SOAPMessageContext.

SDP-25257
Error initializing JAXP DatatypeFactory. Some data types may not be converted correctly.

Category:
Process

Cause:
Could not acquire instance of class javax.xml.datatype.DatatypeFactory. Marshalling/unmarshalling of some XML elements may not happen correctly.

Action:
Ensure that the server's JAXP framework is configured correctly.

SDP-25300
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25301
JNDI context is null.

Category:
Process

Cause:
JNDI context was null.

Action:
See the Javadoc on Oracle Technology Network (OTN) for more information about how to instantiate a JNDI context.

SDP-25302
EJB home for UserPrefsService is null.

Category:
Process

Cause:
EJB home for UserPrefsService is null.

Action:
See the Javadoc on Oracle Technology Network (OTN) for more information about how to specify an EJB home.

SDP-25303
Unable to connect to User Messaging Service (UMS) server at {0}.

Category:
Process

Cause:
EJB Naming Exception was caught when creating a UserPrefsServices object.

Action:
Check the stack trace for more details.

SDP-25304
EJB Remote Exception was caught at server {0}.

Category:
Process

Cause:
EJB Remote Exception was caught.

Action:
Check the stack trace for more details.

SDP-25305
EJB Create Exception was caught at server {0}.

Category:
Process

Cause:
EJB Create Exception was caught.

Action:
Check the stack trace for more details.

SDP-25306
XML Document object is null.

Category:
Process

Cause:
XML Document object is null.

Action:
Specify a valid XML document object.

SDP-25307
No file to upload. File name is not set.

Category:
Process

Cause:
The file name to be uploaded was not set.

Action:
Invoke setFileName() to set the file name.

SDP-25308
The file, {0}, cannot be read.

Category:
Process

Cause:
The file cannot be read.

Action:
Check the file.

SDP-25309
File not found: {0}.

Category:
Process

Cause:
The file with the given file name does not exist.

Action:
Check to see if the path and file name are correct. File name must be in /path/filename or file://path/filename format.

SDP-25311
The document cannot be uploaded. Parser and stack are out of sync. Tag name: {0} Local name: {1}.

Category:
Process

Cause:
The document cannot be uploaded because parser and stack were out of sync.

Action:
Fix mismatched tags.

SDP-25312
Provisioning Exception was caught.

Category:
Process

Cause:
Provisioning Exception was caught.

Action:
Check the stack trace for more details.

SDP-25314
Rule {0} is already defined.

Category:
Process

Cause:
Rule with the same name was already defined.

Action:
Choose a different rule name to avoid conflict.

SDP-25316
Input parameter, UserPrefsServices, is null.

Category:
Process

Cause:
The UserPrefsServices object was null.

Action:
Pass a valid UserPrefsServices object as a parameter. Check User Messaging Service Javadoc on OTN for more information.

SDP-25317
Required input parameter, UserID, is null.

Category:
Process

Cause:
Failed to invoke method, because required input parameter, UserID, is null.

Action:
Pass a valid UserID. Check User Messaging Service Javadoc on OTN for more information.

SDP-25318
Invalid input parameter. DeviceAddress object is null.

Category:
Process

Cause:
Input parameter, DeviceAddress object, is null.

Action:
Pass a valid DeviceAddress object. Check User Messaging Service Javadoc on OTN for more information.

SDP-25319
UserRuleSet is not set. Call initProcessor() first.

Category:
Process

Cause:
UserRuleSet object is null.

Action:
Call initProcessor() first to complete initialization.

SDP-25320
Rule Set is null.

Category:
Process

Cause:
The Rule Set was not available or could not be created.

Action:
Use a valid Rule Set.

SDP-25321
XML String representing the Rule Set is null.

Category:
Process

Cause:
The XML document element representing the Rule Set was null or empty.

Action:
Use a valid Rule Set XML element.

SDP-25322
User Rule Set is null.

Category:
Process

Cause:
The User Rule Set was not available or could not be created.

Action:
Use a valid User Rule Set object.

SDP-25323
User Rule Set is inconsistent. See exception for more details.

Category:
Process

Cause:
User Rule Set is inconsistent.

Action:
Check User Rule Set for consistency.

SDP-25324
XML document is invalid. See exception for details.

Category:
Process

Cause:
XML document is invalid. See stacktrace for more details.

Action:
Validate the XML document.

SDP-25325
Cannot serialize Rule Session.

Category:
Process

Cause:
Cannot serialize Rule Session, which is not critical.

Action:
No action needed.

SDP-25326
Filter XML is null.

Category:
Process

Cause:
The Preference Rules were missing or inconsistent.

Action:
Use a well-formed User Preference XML document.

SDP-25327
Cannot create Rule Session.

Category:
Process

Cause:
Cannot create Rule Session.

Action:
No action needed.

SDP-25328
UserPrefsException was caught.

Category:
Process

Cause:
UserPrefsException was caught.

Action:
Check the stack trace for more details.

SDP-25329
Rule {0} does not exist.

Category:
Process

Cause:
The expected rule was not found.

Action:
Check the rule by name on the User Preference page.

SDP-25330
Business Term Type has changed. Term = {0}.

Category:
Process

Cause:
Business Term Type has changed.

Action:
Recheck the Preference Rules.

SDP-25331
Cannot instantiate User Preferences Services.

Category:
Process

Cause:
Cannot instantiate User Preferences Services due to an initialization error.

Action:
Check User Prefs Services configuration.

SDP-25334
Device name is null.

Category:
Process

Cause:
Device name is null.

Action:
Provide a valid Device name.

SDP-25336
Input parameter, UserPrefsObject, is null.

Category:
Process

Cause:
Required parameter, UserPrefsObject, is null.

Action:
Provide a valid UserPrefsObject.

SDP-25337
Failed to move a rule: origin rule number is out of the range of existing rules.

Category:
Process

Cause:
Origin rule number is not valid.

Action:
Specify a valid rule number.

SDP-25341
The order of calling methods is wrong.

Category:
Process

Cause:
The order of calling methods is wrong.

Action:
Check the order of the methods being called.

SDP-25343
No devices are defined.

Category:
Process

Cause:
Tried to call delivery preferences without defining devices.

Action:
Define devices for use with delivery preferences.

SDP-25344
Invalid action {0} is found and ignored.

Category:
Process

Cause:
An invalid action was detected.

Action:
Use one of the valid actions: BROADCAST, FAIL_OVER, and DO_NOT_SEND.

SDP-25345
Runtime exception was caught.

Category:
Process

Cause:
Runtime exception was caught.

Action:
Check the stack trace for more details.

SDP-25346
No configured Business Terms are available, only system terms will be used.

Category:
Process

Cause:
Business Term configuration could not be read.

Action:
Ensure that business term configuration is correct

SDP-25347
Device {0} cannot be added because it is present in the list.

Category:
Process

Cause:
A device was present in the list already.

Action:
Ensure that the device to be added is not in the device list.

SDP-25348
Failed to move a device: device ID index number is out of the range of device list.

Category:
Process

Cause:
Device ID index number is not valid.

Action:
Specify a valid device ID index number.

SDP-25349
Name of rule is not set.

Category:
Process

Cause:
Rule name was not set.

Action:
Set the name of the rule.

SDP-25350
FilterOperation of a rule is not set.

Category:
Process

Cause:
FilterOperation of a rule was not set.

Action:
Set the FilterOperation of the rule.

SDP-25351
ActionOperation of a rule is not set.

Category:
Process

Cause:
ActionOperation of a rule was not set.

Action:
Set the ActionOperation of the rule.

SDP-25352
Condition of a rule is not set.

Category:
Process

Cause:
Condition of a rule was not set.

Action:
Set the condition of the rule.

SDP-25353
unable to send a BROADCAST message because no address is set.

Category:
Process

Cause:
An address has not been set for the BROADCAST action.

Action:
Set at least one address for the BROADCAST action.

SDP-25354
A failover address is not set for the FAIL_OVER action.

Category:
Process

Cause:
An address has not been set for the FAIL_OVER action.

Action:
Set at least one address for the FAIL_OVER action.

SDP-25356
Cannot persist device address {0} for user GUID {1}, because one already exists.

Category:
Process

Cause:
An identical device address already exists.

Action:
Remove the conflicting device address, overwrite it, or specify a different address.

SDP-25361
The Java VM does not support the encoding {0}.

Category:
Process

Cause:
The Java VM does not support the encoding used for XML string representing the RuleSet.

Action:
Check your server Java VM and make sure it supports the encoding.

SDP-25387
Rule fact for term {0} has been ignored as it does not have the correct type, {1}.

Category:
Process

Cause:
The fact from user or application had an incorrect data type.

Action:
Provide the fact with the correct data type as indicated.

SDP-25388
Device named {0} of user {1} not found.

Category:
Process

Cause:
The user does not have a device with that name.

Action:
Check username and device name.

SDP-25390
Failed to set default address of MESSAGING of user {0}.

Category:
Process

Cause:
Failed to set default address

Action:
Check the stack trace for more details.

SDP-25400
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25403
Error in registering messaging Runtime MBeans.

Category:
Process

Cause:
Exception was thrown.

Action:
Check stack trace

SDP-25404
Error in unregistering messaging Runtime MBeans.

Category:
Process

Cause:
Exception was thrown.

Action:
Check stack trace.

SDP-25405
Naming exception thrown looking up Management Store: Unable to initialize SDP Messaging Runtime MBeans.

Category:
Process

Cause:
Naming exception thrown while looking up the Management Store EJB.

Action:
Check stack trace.

SDP-25406
Create exception thrown while creating Management Store: Unable to initialize SDP Messaging Runtime MBeans.

Category:
Process

Cause:
Create exception thrown while creating Management Store EJB.

Action:
Check stack trace.

SDP-25407
Exception initializing Runtime MBean.

Category:
Process

Cause:
An exception was thrown during runtime MBean initialization.

Action:
Check stack trace.

SDP-25408
Invalid query parameter: query field: {0}, query condition: {1}, query value: {2}.

Category:
Process

Cause:
Invalid combination of query parameters or invalid query value.

Action:
Check stack trace.

SDP-25409
Unable to initialize the composite type for the MBean.

Category:
Process

Cause:
OpenDataException was caught.

Action:
Check stack trace.

SDP-25410
Unable to convert to composite type and return composite data for the MBean. Name: {0}.

Category:
Process

Cause:
OpenDataException was caught.

Action:
Check stack trace.

SDP-25416
Error occurred while attempting to get the parent server MBean for {0}.

Category:
Process

Cause:
An exception was thrown while attempting to get the parent server MBean.

Action:
Check stack trace.

SDP-25500
Failed to schedule Timer.

Category:
Process

Cause:
Timer could not be scheduled in the TimerManager

Action:
Check stack trace, diagnostic dump

SDP-25501
Exception when delivering pending messages.

Category:
Process

Cause:
Exception when delivering pending messages

Action:
Check the stack trace for more details.

SDP-25502
Unable to create JNDI Context.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details. Check the JNDI Context initialization parameters.

SDP-25503
Unable to connect to the messaging server.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details. Check that the messaging server is up. Check the JNDI Context initialization parameters.

SDP-25504
Unable to register application information with the messaging server.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details. Check that the messaging server is up. Check the JNDI Context initialization parameters.

SDP-25505
Unable to enqueue outbound message.

Category:
Process

Cause:
Engine Sending Queue may not be available.

Action:
Check the stack trace for more details.

SDP-25506
Unable to get receiving queues from application information.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details. Check the Application information properties.

SDP-25507
Unable to enqueue inbound message status because no engine queues were found.

Category:
Process

Cause:
The client is not aware of any engine queues to enqueue the status.

Action:
Check that the application is registered successfully with the messaging server.

SDP-25508
Unable to enqueue inbound message status.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25510
An error occurred while attempting to retrieve the actual password from the credential store.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25511
An error occurred while dequeuing a message from the application receiving queue.

Category:
Process

Cause:
An invalid JMS message was dequeued by the Dispatcher MDB.

Action:
Check the stack trace for more details.

SDP-25512
An invalid message was dequeued from the application receiving queue: {0}.

Category:
Process

Cause:
An invalid JMS message was dequeued by the Dispatcher MDB.

Action:
Check the stack trace for more details.

SDP-25513
JNDI lookup of application callback listener failed.

Category:
Process

Cause:
An invalid callback listener was previously registered and could not be invoked.

Action:
Check the stack trace for more details.

SDP-25514
An error occurred while dispatching an inbound message to the application {0}.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25515
An error occurred while dispatching an inbound status to the application {0}.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25516
Message/Status listener not configured. Suspending messaging client MDB to disable asynchronous message/status callbacks.

Category:
Process

Cause:
Message/Status listener was not configured by the application.

Action:
If the application requires asynchronous message/status callbacks, configure the listener information. Otherwise, ignore this warning.

SDP-25517
Messaging client MDB suspend failed: {0}.

Category:
Process

Cause:
1) The Messaging client was unable to access the MDB MBean because the container may not be in RUNNING state. 2) The server administrator username 'weblogic' does not exist.

Action:
1) Check the state of the container. Check the stack trace for more details. 2) Specify a valid server administrator username using the system property -Doracle.ums.admin.user and restart the server.

SDP-25519
QueueWorker rejected.

Category:
Process

Cause:
QueueWorker rejected

Action:
Check WorkManager configuration.

SDP-25524
Client called the deprecated method acknowledge().

Category:
Process

Cause:
The method acknowledge is deprecated.

Action:
Use global transactions instead to achieve reliable message reception.

SDP-25532
An error occurred while retrieving the Application Information from the application JNDI context.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25541
An error occurred while generating received message statuses.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25542
Security principal in client EJB Context "{0}" does not match security principal in ApplicationInfo "{1}". This may cause permission errors during future Messaging Client operations.

Category:
Process

Cause:
The security principal in the current EJBContext is different from the ApplicationInfo security principal field specified when creating the Messaging Client instance (or the default value, if no principal was provided).

Action:
Ensure that the security principals used by this application for all Messaging Client operations match one another.

SDP-25543
The current authenticated user "{0}" does not match the configured security principal "{1}".

Category:
Process

Cause:
The security principal in effect for the current thread is different from the security principal field specified when creating the Messaging Client instance.

Action:
Ensure that the security principals used by this application for all Messaging Client operations match one another, or avoid configuring a specific security principal.

SDP-25700
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25701
Unable to instantiate class {0}.

Category:
Process

Cause:
Unable to instantiate a class.

Action:
Check to see if that class is in classpath or not.

SDP-25702
Unable to set content of Message object.

Category:
Process

Cause:
Unable to set content of a message.

Action:
Check the stack trace for more details.

SDP-25703
Exception when getting cluster name for server {0}.

Category:
Process

Cause:
Could not get cluster name from RuntimeServiceMBean

Action:
Check the stack trace for more details

SDP-25704
Error in setMultiplePayload.

Category:
Process

Cause:
An error occurred in setMultiplePayLoad().

Action:
Check the stack trace for more details.

SDP-25705
Exception printing message content.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25706
Failed to clone message content.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25707
Failed to clone headers. Message = {0}.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25708
Unable to perform JNDI lookup of JMS QCF: {0}.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25709
Unable to perform JNDI lookup.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25710
Exception caught when calling onMessage(), will rollback transaction.

Category:
Process

Cause:
Exception caught when calling onMessage(), will rollback transaction.

Action:
Check log to get more information.

SDP-25711
Received unknown object: {0} on queue {1}.

Category:
Process

Cause:
Received unknown object in JMS queue

Action:
Check log to get more information.

SDP-25712
Message received with invalid format: {0} on queue {1}.

Category:
Process

Cause:
Invalid message received on JMS queue

Action:
Check log to get more information.

SDP-25713
Unable to perform JNDI lookup of JMS Queue: {0}.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25714
Failed to obtaining destination availability for queue with JNDI name: {0}.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-25715
Invalid format, skipping: {0}.

Category:
Process

Cause:
Invalid queue information.

Action:
Check the stack trace for more details.

SDP-25716
Error occurred in looking up QueueConnectionFactory in JNDI, skipping: {0}

Category:
Process

Cause:
Error occurred in looking up QueueConnectionFactory in JNDI.

Action:
Check the stack trace for more details.

SDP-25717
Error occurred in looking up Queue in JNDI, skipping: {0}.

Category:
Process

Cause:
Error occurred in looking up queue in JNDI.

Action:
Check the stack trace for more details.

SDP-25718
Error occurred in getQueueInfoList.

Category:
Process

Cause:
Error occurred in getQueueInfoList().

Action:
Check the stack trace for more details.

SDP-25719
The JMS receiver could not connect to the JMS destination. The error was: {1}. Please ensure the destination is available at the JNDI name {0}. The JMS receiver will periodically attempt to resolve this destination and additional warnings may be issued.

Category:
Process

Cause:
The JMS receiver could not connect to the JMS destination.

Action:
Check the JMS system resource and the JMS server for additional information.

SDP-25725
Message serialization failed.

Category:
Process

Cause:
Failed to serialize message due to I/O Error.

Action:
Ensure that content is being created according to recommendations for Message class.

SDP-25728
Could not determine server platform type. Generic values will be used for platform-specific data.

Category:
Process

Cause:
The Java EE server platform could not be determined. Either this application is executing in a Java SE environment, or the Java EE server is configured incorrectly.

Action:
If executing in a Java SE environment, no action is necessary. Otherwise ensure that Java Required Files module is deployed to this environment.

SDP-25729
An exception occurred while enabling the WS-Security configuration: {0}.

Category:
Process

Cause:
An exception occurred while attaching a WS-Security policy to a web service client or endpoint.

Action:
Ensure that any WS-Security policies are specified in the correct format.

SDP-25730
QueueWorker got exception.

Category:
Process

Cause:
QueueWorker got exception.

Action:
Check the log for related information.

SDP-25731
Failed to find database entry to update. Id: {0}

Category:
Process

Cause:
Failed to find database entry to update.

Action:
Check the stack trace for more details.

SDP-25733
Failed to add/create new QWorker thread {0}

Category:
Process

Cause:
Failed to add/create new QWorker thread {0}.

Action:
Check the stack trace for more details.

SDP-25734
Failed to remove/un-schedule a QWorker thread {0}

Category:
Process

Cause:
Failed to remove/un-schedule a QWorker thread {0}.

Action:
Check the stack trace for more details.

SDP-25900
Exception occurred in config refresh scheduler. Message: {0}

Category:
Process

Cause:
An exception was caught.

Action:
Check the stack trace for more details.

SDP-25901
UMS Config changes found that requires UMS restart. Configs: {0}

Category:
Process

Cause:
Found config changes that requires restart

Action:
Restart Managed server

SDP-25902
Driver reload Failed for driver {0}. Cause {1}

Category:
Process

Cause:
An exception was caught

Action:
Check the stack trace for more details.

SDP-25903
Engine configuration failed to refresh for property {0}. Cause {1}

Category:
Process

Cause:
An exception was caught

Action:
Check the stack trace for more details.

SDP-25904
Timer is requested to stop for Config Refresh scheduler.

Category:
Process

Cause:
Timer is requested to stop

Action:
No Action required.

SDP-25905
Config Refresh scheduler has refreshed the configuration for Properties: {0}

Category:
Process

Cause:
Config Refresh scheduler found difference in configs

Action:
No Action required.

SDP-25906
Unable to initialize config store. Scheduler will not be able to refresh configs. Cause {0}

Category:
Process

Cause:
An exception was caught

Action:
Check the stack trace for more details.

SDP-26000
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26001
Cannot create JNDI Context.

Category:
Process

Cause:
Cannot create JNDI Context.

Action:
Check the stack trace for more details.

SDP-26002
The driver {0} is operational

Category:
Process

Cause:
The driver is operational

Action:
None

SDP-26003
Driver {0} is not configured with required properties. Driver disabled until configured.

Category:
Process

Cause:
Driver was not configured with all required properties.

Action:
Configure this driver.

SDP-26004
No Messaging Engine Queue information to enqueue status.

Category:
Process

Cause:
No Engine Queue information to enqueue status.

Action:
Check that the Engine is deployed. Check Engine Queue information.

SDP-26005
Dispatcher failed to find a driver.

Category:
Process

Cause:
Dispatcher failed to find a driver.

Action:
Compare delivery type and content type between message and available drivers.

SDP-26006
An error occurred while processing an outbound message.

Category:
Process

Cause:
An error occurred while processing an outbound message.

Action:
Check the stack trace for more details.

SDP-26007
No configuration was found for this Driver deployment: {0}. Driver disabled until a configuration is created.

Category:
Process

Cause:
No configuration was found for this Driver deployment.

Action:
Create a configuration this SMPP Driver.

SDP-26008
Invalid configuration for driver {0}. Driver disabled until configured.

Category:
Process

Cause:
Invalid configuration for driver

Action:
Correct the driver configuration.

SDP-26009
Could not get JNDI InitialContext.

Category:
Process

Cause:
None

Action:
None

SDP-26010
Failed to start driver: {0}.

Category:
Process

Cause:
Failed to start driver.

Action:
Check stack trace for more details.

SDP-26011
Failed to register driver in UMS engine: {0}.

Category:
Process

Cause:
Failed to register driver in UMS engine.

Action:
Check stack trace and diagnostic dump for more details.

SDP-26012
Timed out while waiting for SubDrivers to start: {0}.

Category:
Process

Cause:
Timed out while waiting for SubDrivers to start.

Action:
Check stack trace and diagnostic dump for more details.

SDP-26013
Failed to stop driver: {0}.

Category:
Process

Cause:
Unable to stop driver.

Action:
Check stack trace for more details.

SDP-26014
Unable to process inbound message/status.

Category:
Process

Cause:
Exception occurred while processing inbound message/status.

Action:
Check stack trace for more details.

SDP-26015
Unable to process command message.

Category:
Process

Cause:
Exception occurred while processing command message.

Action:
Check stack trace for more details.

SDP-26016
Error occurred while attempting to get the parent server MBean for {0}

Category:
Process

Cause:
Error occurred while attempting to get the parent server MBean

Action:
Check stack trace for more details

SDP-26017
Failed to invoke registerDriverInfo() for driver: {0}

Category:
Process

Cause:
Exception thrown while invoking registerDriverInfo().

Action:
Check stack trace for more details.

SDP-26018
Invalid {0} value: {1}

Category:
Process

Cause:
The driver has been configured with an invalid property value.

Action:
Review the driver configuration and ensure that the property is valid.

SDP-26019
Error occurred while registering driver {0}

Category:
Process

Cause:
Error occurred while registering driver.

Action:
Check stack trace for more details.

SDP-26020
Registration of driver {0} succeeded.

Category:
Process

Cause:
None

Action:
None

SDP-26021
Timed out while waiting for reply from Messaging engine.

Category:
Process

Cause:
The registration command timed out in the JMS queue because the Messaging engine is down or the system is under heavy load.

Action:
Check if the Messaging engine is up and ensure the system is not under extremely heavy load.

SDP-26022
Illegal DeliveryType specified, ignoring type {0}.

Category:
Process

Cause:
Illegal DeliveryType specified.

Action:
Check message delivery type.

SDP-26023
Benchmark logging is enabled for all inbound messages, which may slow down system performance. To disable it, unset environment variable sdpm_inbound_benchmark_logging and restart.

Category:
Process

Cause:
Benchmark logging is enabled when environment variable sdpm_inbound_benchmark_logging=true.

Action:
To disable benchmark logging, unset environment variable sdpm_inbound_benchmark_logging and restart.

SDP-26024
Registration of driver {0} did not complete. Current state is {1}. Will retry periodically until messaging server responds.

Category:
Process

Cause:
None

Action:
None

SDP-26025
Error when registering messaging driver Runtime MBeans for {0}.

Category:
Process

Cause:
Exception was thrown.

Action:
Check stack trace

SDP-26026
Error in unregistering messaging driver Runtime MBeans.

Category:
Process

Cause:
Exception was thrown.

Action:
Check stack trace

SDP-26027
Ignoring property {0} with unsupported Java type {1} during driver initialization.

Category:
Process

Cause:
A property with an unsupported Java type was found in 'usermessagingconfig.xml' during driver initialization.

Action:
Use one of the following valid Java types: java.lang.Boolean, java.lang.String, java.lang.Integer, java.lang.Double, java.lang.Byte, java.lang.Short, java.lang.Long, java.lang.Float, java.lang.Character

SDP-26028
Ignoring property {0} with invalid value {1} and/or Java type {2} during driver initialization.

Category:
Process

Cause:
A property with an invalid value and/or unsupported Java type was found in 'usermessagingconfig.xml' during driver initialization.

Action:
Use a valid value and/or one of the following valid Java types: java.lang.Boolean, java.lang.String, java.lang.Integer, java.lang.Double, java.lang.Byte, java.lang.Short, java.lang.Long, java.lang.Float, java.lang.Character

SDP-26029
Exception occurred during driver configuration initialization for {0}.

Category:
Process

Cause:
An exception occurred during driver configuration initialization.

Action:
Check the stack trace.

SDP-26030
Failed to schedule work {0}

Category:
Process

Cause:
An exception occurred while scheduling a work.

Action:
Check stack trace for more details.

SDP-26031
Lookup of encoded credential value {0} in the credential store for property {1} failed during driver initialization. Passing through the value as-is.

Category:
Process

Cause:
A property with an invalid encoded credential value was found in 'usermessagingconfig.xml' during driver initialization.

Action:
Use a valid encoded credential value and ensure the application has permission grants to access the credential store.

SDP-26032
JNDI lookup of driver connection factory {0} failed with the following error message: {1}. Will retry until successful.

Category:
Process

Cause:
Driver connection factory could not be located in JNDI. Driver registration will not occur until this lookup succeeds.

Action:
Wait for server startup to proceed. If driver registration does not occur, ensure that the driver connection factory JNDI name is configured correctly.

SDP-26033
Started messaging driver: {0}

Category:
Process

Cause:
Driver was started.

Action:
None.

SDP-26034
Stopped messaging driver: {0}

Category:
Process

Cause:
Driver was stopped.

Action:
None.

SDP-26035
JNDI lookup of server command endpoint {0} failed. Will retry until successful.

Category:
Process

Cause:
Messaging Server command module could not be located in JNDI. Driver registration will not occur until this lookup succeeds.

Action:
Wait for server startup to proceed. If driver registration does not occur, ensure that the messaging server is deployed and started.

SDP-26036
Unable to perform JNDI lookup.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26037
Unable to create JMSMessageReceiver

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26038
Failed to retrieve credential from credential store for user {0}

Category:
Process

Cause:
Failed to retrieve credential from credential store for the specified user.

Action:
Check stack trace or error log.

SDP-26039
Driver {0} does not have inbound configuration. No messages (including information about bounced emails) are received.

Category:
Process

Cause:

Action:

SDP-26040
Driver {0} does not have outbound configuration. Messages cannot be sent through this driver.

Category:
Process

Cause:

Action:

SDP-26041
An attempt to configure inbound for driver {0} was detected. All required properties was not configured so the whole configuration (inbound and outbound) will be invalidated. Driver disabled until configured.

Category:
Process

Cause:
An attempt to configure inbound for the driver was detected. All required properties was not configured so the whole configuration (inbound and outbound) will be invalidated. Driver disabled until configured.

Action:
Remove inbound configuration or configure all required properties for this driver.

SDP-26042
An attempt to configure outbound for driver {0} was detected. All required properties was not configured so the whole configuration (inbound and outbound) will be invalidated. Driver disabled until configured.

Category:
Process

Cause:
An attempt to configure outbound for the driver was detected. All required properties was not configured so the whole configuration (inbound and outbound) will be invalidated. Driver disabled until configured.

Action:
Remove outbound configuration or configure all required properties for this driver.

SDP-26043
Driver {0} lost connection to the external gateway. Will try to reconnect.

Category:
Process

Cause:

Action:

SDP-26044
Driver {0} reconnected to the external gateway.

Category:
Process

Cause:

Action:

SDP-26100
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26101
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26102
Error while writing e-mail message content.

Category:
Process

Cause:
An exception has occurred while writing e-mail content and headers to an e-mail message.

Action:
Check stack trace or error log.

SDP-26103
Error while writing e-mail subject.

Category:
Process

Cause:
Cannot write the subject.

Action:
Check stack trace or error log.

SDP-26104
Recipient address error.

Category:
Process

Cause:
Recipient e-mail address has an error.

Action:
Check and see if the recipient e-mail address is correct.

SDP-26105
Unable to deliver to following address(es): {0} Reason: {1}

Category:
Process

Cause:
One or more recipient e-mail addresses had an error.

Action:
Ensure that the e-mail address is correct.

SDP-26106
Failed to send the e-mail message

Category:
Process

Cause:
Unable to login to SMTP server.

Action:
Check SMTP server host name, port, user name, and password.

SDP-26107
Failed to add header - name: {0} value: {1}

Category:
Process

Cause:
Unable to add an e-mail header to a multipart message

Action:
Check the stack trace or error log.

SDP-26108
Content type parsing error {0}.

Category:
Process

Cause:
Error occurred while trying to parse the content type.

Action:
Check and see if the content type is specified correctly.

SDP-26109
Caught exception while closing connection to e-mail server.

Category:
Process

Cause:
An exception was caught while closing connection.

Action:
Check stack trace or error log.

SDP-26110
Failed to start Email Driver

Category:
Process

Cause:
Failed to start Email Driver.

Action:
Check stack trace or error log. Check e-mail driver parameters and make sure all email servers are running.

SDP-26111
Failed to retrieve credential from credential store for user {0}

Category:
Process

Cause:
Failed to retrieve credential from credential store for the specified user.

Action:
Check stack trace or error log.

SDP-26112
Authentication failed: user={0}, host={1}:{2}, sslEnabled={3}

Category:
Process

Cause:
Authentication failed for the specified user, server, port, and sslEnabled parameters.

Action:
Check stack trace or error log. Check the username, password, server, port, and sslEnabled parameters.

SDP-26118
Failed to open folder {0} for user {1}

Category:
Process

Cause:
Folder name is not correct or does not exist.

Action:
Check folder name spelling.

SDP-26119
Max retry limit reached for trying to connect to user {0}

Category:
Process

Cause:
Email driver has reached Max retry limit to connect to user.

Action:
Check stack trace or error log. Check e-mail driver parameters and make sure all servers are up.

SDP-26122
An exception has been thrown when connecting to user {0}

Category:
Process

Cause:
Email driver could not connect to user.

Action:
Check username and password. Make sure the user exists and is accessible.

SDP-26123
Could not initialize Email Store for: user {0}, server {1}, folder {2}, sslEnabled {3}

Category:
Process

Cause:
Could not initialize Email Store for the specified user, server, folder, and sslEnabled parameters.

Action:
Check stack trace or error log. Check the username, password, server, folder and sslEnabled parameters.

SDP-26126
Unrecoverable message - {0}

Category:
Process

Cause:
failed to recover an e-mail message

Action:
Check stack trace or error log.

SDP-26130
Ignoring property {0} with invalid value {1} during driver initialization.

Category:
Process

Cause:
A property with an invalid value was found in 'usermessagingconfig.xml' during driver initialization.

Action:
Ensure the value configured value is valid.

SDP-26131
Lookup of encoded credential value {0} in the credential store for property {1} failed during driver initialization.

Category:
Process

Cause:
A property with an invalid encoded credential value was found in 'usermessagingconfig.xml' during driver initialization.

Action:
Use a valid encoded credential value and ensure the application has permission grants to access the credential store.

SDP-26134
Email Driver {0} is not configured with incoming mail properties. No emails (including information about bounced emails) are received.

Category:
Process

Cause:

Action:

SDP-26135
Email Driver {0} is not configured with outgoing mail properties. Emails cannot be sent through this driver.

Category:
Process

Cause:

Action:

SDP-26136
Driver property OutgoingDefaultFromAddr is deprecated. Use DefaultSenderAddress instead.

Category:
Process

Cause:
Driver property OutgoingDefaultFromAddr in 'usermessagingconfig.xml' is deprecated.

Action:
Use DefaultSenderAddress instead.

SDP-26137
Both DefaultSenderAddress and the deprecated OutgoingDefaultFromAddr is configured in 'usermessagingconfig.xml'. DefaultSenderAddress will be used.

Category:
Process

Cause:
Both OutgoingDefaultFromAddr and DefaultSenderAddress is configured in 'usermessagingconfig.xml'. DefaultSenderAddress will be used.

Action:
Remove configuration for OutgoingDefaultFromAddr.

SDP-26138
Message was not delivered. No valid sender(From) address available.

Category:
Process

Cause:
No sender address set in message and DefaultSenderAddress is not configured in 'usermessagingconfig.xml'.

Action:
Set sender(From) address in message or set DefaultSenderAddress in 'usermessagingconfig.xml'.

SDP-26450
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26451
One or more sets of extension endpoints were configured using identical protocols and mapped domains: {0}.

Category:
Process

Cause:
Each of the listed protocol/domain pairs is used to configure multiple extension endpoints.

Action:
Remove the conflicting endpoint configuration, or ensure that each endpoint has unique protocol and mapped domain parameters.

SDP-26452
No extension endpoint could be found for the specified recipient address.

Category:
Process

Cause:
None of the configured extension endpoints matched the protocol and domain of the message recipient.

Action:
Ensure that an endpoint is configured for the desired protocol and domain, or configure a default (empty) domain.

SDP-26453
No configuration was found for this Extension Driver deployment: {0}. Driver disabled until a configuration is created.

Category:
Process

Cause:
No configuration was found for this Email Driver deployment.

Action:
Create a configuration this Email Driver.

SDP-26454
Extension Driver {0} is not configured with at least one extension point with a valid endpoint URL and protocol. Driver disabled until configured.

Category:
Process

Cause:
Extension Driver is not configured with at least one extension point with a valid endpoint URL and protocol.

Action:
Configure this driver.

SDP-26455
Error while processing Extension Driver configuration with Endpoint URL: {0}. The configuration must contains a valid endpoint URL and protocol.

Category:
Process

Cause:
An error occurred while processing the Extension Driver configuration.

Action:
Check the corresponding configuration. The configuration must contains a valid endpoint URL and protocol.

SDP-26456
An exception occurred while enabling the WS-Security configuration: {0}

Category:
Process

Cause:
An exception occurred while attaching a WS-Security policy to a web service client or endpoint.

Action:
Ensure that any WS-Security policies are specified in the correct format.

SDP-26457
An exception occurred while constructing the SOAP message: {0}

Category:
Process

Cause:
An exception occurred while constructing the SOAP message

Action:
Check the configuration of the server.

SDP-26550
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26551
Failed to deliver a message to the gateway at {0}. No Status could be generated for the failed message.

Category:
Process

Cause:
A message failed to be delivered to the gateway.

Action:
Check the connectivity to the gateway

SDP-26150
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26151
Failed to process a received message in SMPP driver, because driver context is null

Category:
Process

Cause:
Driver context is null

Action:
Check the stack trace for more details.

SDP-26152
WorkManager object is null in SMPP driver.

Category:
Process

Cause:
The caller of setWorkManager() passed in a null WorkManager object as an argument

Action:
Make sure WorkManager object is not null.

SDP-26153
Failed to connect to server, host: {0}, port: {1} (local address: {2}, local port: {3})

Category:
Process

Cause:
Failed to connect to server with the specified parameters.

Action:
Check the stack trace and the specified parameters. Ensure that the network is operational.

SDP-26155
unable to initialize SMPP driver, because a driver attribute, sms.account.id, is not set.

Category:
Process

Cause:
The account ID was not set.

Action:
Set the correct account information.

SDP-26156
Failed to initialize SMPP Driver because driver attributes sms.server.host, sms.server.transmitter.port or sms.server.receiver.port is not set.

Category:
Process

Cause:
SMSC server or account information is not correct or missing.

Action:
Check those parameters.

SDP-26158
Caught exception while closing connection

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26159
Illegal data length value from SMSC received and ignored: {0}

Category:
Process

Cause:
SMPP Driver has detected a corrupted data field from SMSC and it is trying to recover.

Action:
This error suggests communication errors between SMPP driver and SMSC. Check to see if this driver supports that SMSC.

SDP-26160
No configuration was found for this SMPP Driver deployment: {0}. Driver disabled until a configuration is created.

Category:
Process

Cause:
No configuration was found for this SMPP Driver deployment.

Action:
Create a configuration this SMPP Driver.

SDP-26161
Starting SMPP Driver: {0}

Category:
Process

Cause:
SMPP Driver resource adapter initialization.

Action:
None

SDP-26163
Data stream ended unexpectedly while reading packet from SMSC

Category:
Process

Cause:
The data stream ended unexpectedly while reading a packet from the SMSC. Message or command will be dropped.

Action:
None.

SDP-26164
Failed to bind receiver connection; will retry until bind operation is successful.

Category:
Process

Cause:
Could not bind to the SMSC as a receiver. Bind operation will be retried periodically until it is successful.

Action:
None required. Change value of configuration parameter "BindRetryDelay" to adjust retry interval.

SDP-26165
Lookup of encoded credential value for account {0} in the credential failed during driver initialization.

Category:
Process

Cause:
Lookup of encoded credential value in the credential failed during driver initialization.

Action:
Check the stack trace for more details. Ensure that the encoded indirect password and the credential store are properly configured.

SDP-26166
SMPP Driver {0} is not configured with all required properties. Driver disabled until configured.

Category:
Process

Cause:
SMPP Driver was not configured with all required properties.

Action:
Configure this driver.

SDP-27001
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-27002
Failed to deliver a message to the gateway at {0}. No Status could be generated for the failed message.

Category:
Process

Cause:
A message failed to be delivered to the gateway.

Action:
Check the connectivity to the gateway

SDP-27003
Invalid Credentials provided. {0}

Category:
Process

Cause:
Invalid Credentials provided

Action:
Check the credentials

SDP-27004
Not Found returned from API call please check message. {0}

Category:
Process

Cause:
Not Found returned from API.

Action:
Check the logs for details

SDP-27005
Message Payload contains Invalid data, cause: {0}

Category:
Process

Cause:
Message Payload contains Invalid data.

Action:
Check the message for details.

CLONE-92100
In method doCopyConfigValidation.

Category:
Process

Cause:

Action:

CLONE-92101
In method doCopyConfig.

Category:
Process

Cause:

Action:

CLONE-92102
In method doPostCopyConfig..

Category:
Process

Cause:

Action:

CLONE-92103
In method doPasteConfigValidation.

Category:
Process

Cause:

Action:

CLONE-92104
In method doPrePasteConfig.

Category:
Process

Cause:

Action:

CLONE-92105
In method doPasteConfig.

Category:
Process

Cause:

Action:

CLONE-92106
In method doPostPasteConfig.

Category:
Process

Cause:

Action:

CLONE-92107
Download data for User Preferences.

Category:
Process

Cause:

Action:

CLONE-92109
Extract driver configuration.

Category:
Process

Cause:

Action:

CLONE-92110
Extract configuration from {0}.

Category:
Process

Cause:

Action:

CLONE-92111
Value was null for property {0}. Skip.

Category:
Process

Cause:

Action:

CLONE-92112
No UMS config found. Skip driver configuration.

Category:
Process

Cause:

Action:

CLONE-92113
Update configuration on {0}.

Category:
Process

Cause:

Action:

CLONE-92114
Upload data for User Preferences.

Category:
Process

Cause:

Action:

CLONE-92115
UMS application not present in domain. Skip doCopyConfig (no-op).

Category:
Process

Cause:

Action:

CLONE-92116
UMS application not present in domain. Skip doPasteConfig (no-op).

Category:
Process

Cause:

Action:

CLONE-92117
Starting server {0}.

Category:
Process

Cause:

Action:

CLONE-92118
Stopping server {0}.

Category:
Process

Cause:

Action:

CLONE-92119
Handle User Preferences.

Category:
Process

Cause:

Action:

CLONE-92120
Found User Preferences on {0}.

Category:
Process

Cause:

Action:

CLONE-92130
No DriverConfigExtractor found for driver type {0}. Skip.

Category:
Process

Cause:

Action:

CLONE-92300
doCopyConfig failed. msg={0} stackTrace={1}

Category:
Process

Cause:
Failure during copyConfig.

Action:
See log for details.

CLONE-92301
doPasteConfig failed. msg={0} stackTrace={1}

Category:
Process

Cause:
Failure during pasteConfig.

Action:
See log for details.

CLONE-92302
Skipped corrupted ConfigGroup for {0}

Category:
Process

Cause:
Expected one ConfigProperty within ConfigGroup.

Action:
Edit moveplan.xml or configure manually in the production system.

SDP-26300
A Twitter exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26301
Got an exception when receiving tweets.

Category:
Process

Cause:
An exception has occurred when receiving tweets.

Action:
Check the stack trace for more details.

SDP-26302
Got an exception when receiving direct messages.

Category:
Process

Cause:
An exception has occurred when receiving direct message.

Action:
Check the stack trace for more details.

SDP-26303
Exception caught during attributes transferring of an inbound direct message.

Category:
Process

Cause:
An exception has occurred when transferring attributes of a direct message.

Action:
Check the stack trace for more details.

SDP-26304
Exception caught during attributes transferring of an inbound tweet.

Category:
Process

Cause:
An exception has occurred when transferring attributes of a tweet.

Action:
Check the stack trace for more details.

SDP-26305
Got an exception when building an inbound UMS message from a received tweet or direct message.

Category:
Process

Cause:
An exception has occurred when rebuilding an inbound UMS message.

Action:
Check the stack trace for more details.

SDP-26306
Required OAuth login information is missing or incomplete. Consumer key, consumer secret, access token, and/or access token secret is not set.

Category:
Process

Cause:
At least one of Twitter consumer key, consumer secret, access token, and access token secret is missing or not set.

Action:
Check the log file for the missing field(s).

SDP-26307
Required xAuth login information for user {0} is missing or incomplete. Both username and password are required.

Category:
Process

Cause:
Username or password is missing or not set.

Action:
Check the log file for the missing field(s).

SDP-26308
No configuration was found for this Twitter Driver deployment: {0}. Driver disabled until a configuration is created.

Category:
Process

Cause:
No configuration was found for this Twitter Driver deployment.

Action:
Create a configuration this Twitter Driver.

SDP-26309
Twitter Driver {0} is not configured with all required properties. Driver disabled until configured.

Category:
Process

Cause:
Twitter Driver was not configured with all required properties.

Action:
Configure this driver.

SDP-26310
Twitter Driver not properly configured. AuthenticationMode {0} is unknown and not supported.

Category:
Process

Cause:
Twitter Driver not properly configured. AuthenticationMode given is unknown and not supported.

Action:
Configure and restart this driver.

SDP-26311
Retweet id string {0} in meta data could not be converted to long. No tweet for messageId {1}

Category:
Process

Cause:
Retweet id string in meta data could not be converted to long.

Action:
Check how the application generates the meta data.

SDP-26312
Ignoring reply id string {0} in meta data that could not be converted to long.

Category:
Process

Cause:
Ignoring reply id string in meta data that could not be converted to long.

Action:
Check how the application generates the meta data.

SDP-26313
Ignoring geo location string ({0}) in meta data that could not be converted to (double,double).

Category:
Process

Cause:
Ignoring geo location string in meta data that could not be converted to (double,double).

Action:
Check how the application generates the meta data.

SDP-26314
Failed to verify the credentials.

Category:
Process

Cause:
Failed to verify the credentials.

Action:
Check the Twitter Driver configuration.

SDP-26315
Failed to send tweet due to rate limitation.

Category:
Process

Cause:
Failed to send tweet due to rate limitation.

Action:
Adjust the send rate or modify the Twitter Account settings.

SDP-26316
Failed to receive tweet due to rate limitation.

Category:
Process

Cause:
Failed to receive tweet due to rate limitation.

Action:
Wait or modify the Twitter Account settings.

SDP-26317
Twitter exception when sending tweet. Msg={0}

Category:
Process

Cause:
Twitter exception when sending tweet.

Action:
Check the Twitter Exception message.

SDP-25800
Oracle User Messaging Service configuration is successfully upgraded.

Category:
Process

Cause:

Action:

SDP-25801
Shall upgrade driver {0} using configuration file at {1}.

Category:
Process

Cause:

Action:

SDP-25802
Driver {0} upgraded using {1}.

Category:
Process

Cause:

Action:

SDP-25803
Driver {0} already upgraded. Ignoring configuration in {1}.

Category:
Process

Cause:

Action:

SDP-25804
Shall upgrade server {0} using configuration file at {1}.

Category:
Process

Cause:

Action:

SDP-25805
Server {0} upgraded using {1}.

Category:
Process

Cause:

Action:

SDP-25806
Server {0} already upgraded. Ignoring configuration in {1}.

Category:
Process

Cause:

Action:

SDP-25807
Shall upgrade user preference configuration for {0} using file at {1}.

Category:
Process

Cause:

Action:

SDP-25808
User preference configuration for {0} upgraded using {1}.

Category:
Process

Cause:

Action:

SDP-25809
Invalid managed server entered. Continue upgrade to see if we still can do a remote copy of the 11g configuration files.

Category:
Process

Cause:

Action:

SDP-25810
Custom deployed UMS application {0} will be deleted from the domain.

Category:
Process

Cause:
Custom deployed UMS applications are not supported any longer.

Action:

SDP-25811
Failed to read configuration for driver {0}, {1}. Probably due to targeted driver without configuration.

Category:
Process

Cause:

Action:

SDP-25812
Ignoring configuration for application {0}.

Category:
Process

Cause:

Action:

SDP-25820
Error in upgrading Oracle User Messaging Service configuration. Reason: {0}

Category:
Process

Cause:
An unexpected error occurred during Oracle User Messaging Service configuration upgrade.

Action:
Check the error messages in the log file. Correct the problem before running the Upgrade Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

SDP-25821
Failed to read the configuration file {0}.

Category:
Process

Cause:
The configuration file is missing or in wrong format.

Action:
Check if the configuration file exists with correct format. Correct the problem before running the Upgrade Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

SDP-25822
Failed to save the configuration at {0}.

Category:
Process

Cause:
Error occured while saving the configuration to the configuration file.

Action:
Check the error messages in the log file. Correct the problem before running the Upgrade Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

SDP-25823
Failed to delete the old configuration file at {0}.

Category:
Process

Cause:
Error occurred while deleting the old configuration file.

Action:
Check the file system. Correct the problem before running the Upgrade Assistant again.

SDP-25824
Failed to parse the configuration file at {0}.

Category:
Process

Cause:
Error occured while parsing the configuration file.

Action:
Check the error messages in the log file. Correct the problem before running the Upgrade Assistant again.

SDP-25825
Error during copy of configuration files from remote managed server {0}.

Category:
Process

Cause:
Old 11g configuration files where due to some problem not copied correct to the AdminServer. It could be that the plugin is missing information needed to connect to and copy the configuration from one of the managed servers. Or it could be that the sshd is not running on all the managed servers.

Action:
Check the error messages in the log file to see what the problem is. Correct the problem before running the Upgrade Assistant again or perform a manual copy of the old configuration from the remote managed servers to the AdminServer.

SDP-25826
Error connecting to remote managed server {0}.

Category:
Process

Cause:
It could be that the plugin is missing information needed to connect to one of the managed servers. Or it could be that the sshd is not running on all the managed servers.

Action:
Check the error messages in the log file to see what the problem is. Correct the problem before running the Upgrade Assistant again or perform a manual copy of the old configuration from the remote managed servers to the AdminServer.

SDP-25827
Neither the configuration nor the data entered by the user provides all information needed to copy the UMS 11g configuration files.

Category:
Process

Cause:
Upgrade Assistant does not have all information about the remote managed servers to be able to connect and copy the UMS 11g configuration files.

Action:
Make sure to fill in name and address for all remote managed Servers that does not have this information configured.

SDP-25850
Oracle User Messaging Service schema upgraded.

Category:
Process

Cause:

Action:

SDP-25851
Oracle User Messaging Service schema upgrade is valid.

Category:
Process

Cause:

Action:

SDP-25852
Oracle User Messaging Service schema version {0} is the latest one. Upgrade is not required.

Category:
Process

Cause:
Specified Oracle User Messaging Service database schema version is the latest one. Upgrade is not required.

Action:
No user action is required.

SDP-25853
Oracle User Messaging Service schema upgrade is invalid.

Category:
Process

Cause:
Specified User Messaging Service schema was updated but is invalid.

Action:
Restore the User Messaging Service schema from a backup and retry. Check the error messages in Oracle User Messaging Service component log files. Correct the problem before running the Upgrade Assistant again.

SDP-25854
The upgrade is not supported from Oracle User Messaging Service schema version of {0}.

Category:
Process

Cause:
An unsupported base schema version was being upgraded.

Action:
Refer to the Oracle User Messaging Service Upgrade Guide for supported versions to upgrade.

SDP-25855
Error in upgrading Oracle User Messaging Service schema. {0}

Category:
Process

Cause:
An unexpected error occurred during Oracle User Messaging Service schema upgrade.

Action:
Check the error messages in the log file. Correct the problem before running the Upgrade Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

SDP-25856
Oracle User Messaging Service schema status is invalid.

Category:
Process

Cause:
Specified Oracle User Messaging Service database schema was invalid.

Action:
Check the error messages in the log file. Correct the problem before running the Upgrade Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

SDP-25857
Error in Oracle User Messaging Service schema readiness check.

Category:
Process

Cause:
An unexpected error occurred during Oracle User Messaging Service schema readiness check.

Action:
Check the error messages in the log file. Correct the problem before running the Upgrade Assistant again. Contact Oracle Support Services if you are unable to correct the problem.

SDP-26200
An exception was caught.

Category:
Process

Cause:
An exception has occurred.

Action:
Check the stack trace for more details.

SDP-26205
Exception while getting content from message with id={0}

Category:
Process

Cause:
Exception while getting content from message.

Action:
Check the stack trace for more details.

SDP-26213
Exception while sending message - from: {0} to: {1}.

Category:
Process

Cause:
Exception while sending message.

Action:
Check stack trace and recipient address

SDP-26214
Caught an exception in XMPP driver while sending out a message.

Category:
Process

Cause:
An exception was caught.

Action:
Check the stack trace for more details.

SDP-26225
Received Error Message. Code: {0} Text: {1}.

Category:
Process

Cause:
Received Error Message.

Action:
Check error code and error message.

SDP-26236
Got an exception when receiving a message.

Category:
Process

Cause:
Got an exception when receiving a message.

Action:
Check to see if the message is well-formed.

30

SOAPWS-JMS-225010 to SOAPWS-JMS-225012

SOAPWS-JMS-225010
Error starting the JMS listener {0} {1}

Category:
WebService

Cause:
Cannot start JMS listener

Action:
Please check the JMS configuration.

SOAPWS-JMS-225011
Error closing JMS connection {0} {1}

Category:
WebService

Cause:
Cannot close JMS connection

Action:
Please check the JMS configuration.

SOAPWS-JMS-225012
JMS onMessage exception {0} {1}

Category:
WebService

Cause:
Exception in processing JMS onMessage

Action:
Please check the exception cause details.

31

TCM-00006 to TCM-99009

TCM-00006
The NameId for the request is not valid.

Category:
Requests/Responses

Cause:
The NameId for a service request did not contain a Name or an Identifier.

Action:
Provide either a Name or an Identifier for a service request.

TCM-00007
The Id for the request is not valid.

Category:
Requests/Responses

Cause:
The document identifier for the request was not valid. The value supplied was null or an empty string.

Action:
Provide a valid document identifier for a document service request.

TCM-00008
The SectionFlags for the request are not valid.

Category:
Programmatic

Cause:
The wrong section flags were provided for the request.

Action:
Consult the API documentation for the proper section flags for the request.

TCM-00009
No session has been established.

Category:
Requests/Responses

Cause:
A session was expected to exist but was not found. This may occur if operations were called after logging out.

Action:
Log in and properly establish a session before attempting an operation.

TCM-00010
The version of the JRE used by the repository is too low to support Imaging. The required minimum is {0}. The repository is using {1}.

Category:
Configuration

Cause:
An attempt was made to establish a connection to a Content Server repository using the wrong JRE.

Action:
Upgrade the Content Server JRE to the minimum required version. The required version will be stated in the error message.

TCM-00013
Basic Authentication requires SSL.

Category:
Configuration

Cause:
An attempt was made to log in to imaging without using SSL, which is required.

Action:
Configure the imaging server for SSL and use https in the web services URL.

TCM-00015
Unable to find file {0}

Category:
Requests/Responses

Cause:
A file used for input could not be found.

Action:
Check the file path given in the error message and verify that it exists.

TCM-00016
Unable to open file {0}

Category:
Requests/Responses

Cause:
A file used for input could not be opened.

Action:
Check the file path given in the error message and verify that it is readable.

TCM-00020
Unable to authenticate user.

Category:
Requests/Responses

Cause:
Invalid credentials were supplied during login.

Action:
Provide valid credentials.

TCM-00021
This session is already established.

Category:
Requests/Responses

Cause:
An attempt was made to log in to a session that was already established.

Action:
Either use the existing session without logging in again, or log out to establish a new session.

TCM-00022
Service was called without credentials. The calling user cannot be authenticated.

Category:
Requests/Responses

Cause:
No credentials were provided for the service request.

Action:
Ensure the proper security credentials are applied to the login services.

TCM-00026
The requested definition is not found.

Category:
Requests/Responses

Cause:
The definition requested does not exist. The user does not have access to the definition.

Action:
Check the requested definition name or identifier for correctness. Check the user's access to the requested definition.

TCM-00027
User does not have permission to access this page.

Category:
Requests/Responses

Cause:
An attempt was made to access a definition page that the user does not have permission to access.

Action:
Check the user's permissions to the requested definition.

TCM-00028
The definition arrays supplied are empty.

Category:
Programmatic

Cause:
The definitions supplied for an import or export operation were empty arrays.

Action:
Make sure that the definitions arrays are filled in with valid definition NameIds.

TCM-00029
The {0} section is read-only and cannot be modified.

Category:
Programmatic

Cause:
At least one definition section specified for modify was read only and cannot be changed.

Action:
Remove the read-only section from the modify section set argument.

TCM-00030
Invalid date string: {0}

Category:
Requests/Responses

Cause:
The value that was parsed was not a supported date format.

Action:
Fix the value so that it is a supported date format.

TCM-00031
Invalid group, the groupPrincipalHolder is null!

Category:
Requests/Responses

Cause:
The groupPrincipalHolder is null!

Action:
If using Active Directory please verify that the security provider "Use Token Groups for Group Membership Lookup" is disabled or that the configured security provider user accessing Active Directory has tokenGroups privileges to the LDAP.

TCM-00040
Encountered exception initializing regions.

Category:
Requests/Responses

Cause:

Action:

TCM-00041
Cache is Ready = {0}

Category:
Requests/Responses

Cause:

Action:

TCM-00042
Cache Distributed = {0}

Category:
Requests/Responses

Cause:

Action:

TCM-00043
Imaging region exists.

Category:
Requests/Responses

Cause:

Action:

TCM-00044
Cache failed during initialization and may be disabled.

Category:
Requests/Responses

Cause:

Action:

TCM-00045
The cache age limit must be set to a positive number

Category:
Requests/Responses

Cause:

Action:

TCM-00102
Workflow Agent login failure.

Category:
Requests/Responses

Cause:
The Workflow Agent failed to log in.

Action:
Review the server logs for further information.

TCM-00103
Workflow Agent logout failure.

Category:
Requests/Responses

Cause:
The Workflow Agent failed to log out.

Action:
Review the server logs for further information.

TCM-00104
Workflow Agent error processing a message.

Category:
Requests/Responses

Cause:
An error occurred trying to process a worklfow agent message.

Action:
Review the server logs for further information.

TCM-00105
Document {0} returning to workflow agent queue for retry.

Category:
Requests/Responses

Cause:

Action:

TCM-00106
Workflow agent processing fault recorded for document {0}.

Category:
Requests/Responses

Cause:
An error was encountered processing a document. The document was identified in the error message. The error could be due to the workflow server being down.

Action:
Review the server logs for further information. The workflow agent will attempt to reprocess the document.

TCM-00107
Workflow agent cannot record fault for document {0}. Returning to workflow agent queue for retry.

Category:
Requests/Responses

Cause:
An error was encountered processing a document, and the workflow agent was unable to record the error as a fault. The document was identified in the error message.

Action:
Review the server logs for further information. The workflow agent will attempt to reprocess the document.

TCM-00110
Constructed Input Agent Bean.

Category:
Requests/Responses

Cause:

Action:

TCM-00111
Destroyed Input Agent Bean.

Category:
Requests/Responses

Cause:

Action:

TCM-00112
Input Agent encountered an error during shutdown.

Category:
Requests/Responses

Cause:

Action:

TCM-00113
An error occurred trying to read the Input Agent configuration.

Category:
Requests/Responses

Cause:
An error occurred trying to read the Input Agent Bean configuration.

Action:
Review the server logs for further information.

TCM-00114
An error occurred initializing the Input Agent Bean.

Category:
Requests/Responses

Cause:
An error occurred initializing the Input Agent Bean.

Action:
Review the server logs for further information.

TCM-00115
Beginning Input Agent initialization.

Category:
Requests/Responses

Cause:

Action:

TCM-00116
Input Agent initialization is complete.

Category:
Requests/Responses

Cause:

Action:

TCM-00118
Input Agent timer service is not initialized. Cannot continue.

Category:
Requests/Responses

Cause:
Input Agent timer service is not initialized.

Action:
Check the Application Server installation and restart the service.

TCM-00119
Input Agent configuration is empty. Cannot continue.

Category:
Requests/Responses

Cause:
Input Agent configuration is empty.

Action:
Check the JDBC connection and reboot the server.

TCM-00120
Input Agent time interval is not set. Cannot continue.

Category:
Requests/Responses

Cause:
Input Agent time interval is not set.

Action:
Update the Check Interval setting to a valid value in the WebCenter Content: Imaging config MBean.

TCM-00121
An error occurred resetting an input job.

Category:
Requests/Responses

Cause:
An error occurred resetting an input job.

Action:
Review the server logs for further information.

TCM-00122
An error occurred checking for work.

Category:
Requests/Responses

Cause:

Action:

TCM-00126
Beginning Input Agent servlet initialization.

Category:
Requests/Responses

Cause:

Action:

TCM-00127
Input Agent servlet initialization is complete.

Category:
Requests/Responses

Cause:

Action:

TCM-00128
The JMS Queue browser cannot be closed properly.

Category:
Requests/Responses

Cause:
There was a problem closing the JMS Queue browser.

Action:
Review the server logs for more information.

TCM-00129
Input Agent is checking for work.

Category:
Requests/Responses

Cause:

Action:

TCM-00130
Beginning Input Agent Cleanup timer initialization.

Category:
Requests/Responses

Cause:

Action:

TCM-00131
Input Agent Cleanup timer initialization is complete.

Category:
Requests/Responses

Cause:

Action:

TCM-00132
Input Agent Cleanup is looking for expired images.

Category:
Requests/Responses

Cause:

Action:

TCM-00150
Constructed Input Filing MDB.

Category:
Requests/Responses

Cause:

Action:

TCM-00151
Destroyed Input Filing MDB.

Category:
Requests/Responses

Cause:

Action:

TCM-00152
Error while unregistering Input Filing MDB.

Category:
Requests/Responses

Cause:
An error occurred while unregistering Input Filing MDB.

Action:
Review the server logs for further information.

TCM-00153
Beginning filing for Input {0} and data source {1}.

Category:
Requests/Responses

Cause:

Action:

TCM-00154
Filing {0} completed successfully with {1} documents processed successfully out of {2} documents.

Category:
Requests/Responses

Cause:

Action:

TCM-00155
Filing {0} failed with {1} documents that failed to index.

Category:
Requests/Responses

Cause:

Action:

TCM-00156
Error indexing document number {0}.

Category:
Requests/Responses

Cause:
An error occurred while indexing a document.

Action:
Review the server logs for further information.

TCM-00157
An error occurred filing file {0}.

Category:
Requests/Responses

Cause:
An error occurred while filing a job.

Action:
Review the server logs for further information.

TCM-00158
Failed to cancel job.

Category:
Requests/Responses

Cause:
Failed to cancel a job.

Action:
Review the server logs for further information.

TCM-00159
Cannot determine what Input Source to use for job and cannot abort or cancel job.

Category:
Requests/Responses

Cause:

Action:

TCM-00160
Input Filing MDB failed to log out.

Category:
Requests/Responses

Cause:

Action:

TCM-00161
Failed to resume filing for data source {0} and batch {1}.

Category:
Requests/Responses

Cause:

Action:

TCM-00162
Failed to load Batch for new filing.

Category:
Requests/Responses

Cause:

Action:

TCM-00163
An error occurred while completing a batch.

Category:
Requests/Responses

Cause:

Action:

TCM-00164
Input Agent cannot find WLS Runtime MBean server.

Category:
Requests/Responses

Cause:

Action:

TCM-00165
The Input {0} is currently marked offline, so the request to process data source {1} is being rolled back

Category:
Requests/Responses

Cause:

Action:

TCM-00166
Resubmitting job for input source {0} due to error: {1}

Category:
Requests/Responses

Cause:

Action:

TCM-00170
Constructed Ticket Agent MDB.

Category:
Requests/Responses

Cause:

Action:

TCM-00171
Destroyed Ticket Agent MDB.

Category:
Requests/Responses

Cause:

Action:

TCM-00172
Beginning Ticket Agent servlet initialization.

Category:
Requests/Responses

Cause:

Action:

TCM-00173
Ticket Agent servlet initialization is complete.

Category:
Requests/Responses

Cause:

Action:

TCM-00174
An error occurred while restarting the Ticket Agent MDB.

Category:
Requests/Responses

Cause:
An error occurred while restarting the Ticket Agent MDB.

Action:
Review the server logs for further information.

TCM-00175
Ticket Agent timer service is not initialized. Cannot continue.

Category:
Requests/Responses

Cause:
Ticket Agent timer service is not initialized.

Action:
Check the Application Server configuration and restart the service

TCM-00176
An error occurred while initializing Ticket Agent MDB.

Category:
Requests/Responses

Cause:
An error occurred while initializing Ticket Agent MDB.

Action:
Review the server logs for further information.

TCM-00177
Beginning Ticket Agent initialization.

Category:
Requests/Responses

Cause:

Action:

TCM-00178
Ticket Agent initialization is complete.

Category:
Requests/Responses

Cause:

Action:

TCM-00179
Encountered an error while attempting to clean up expired tickets from the imaging system

Category:
Requests/Responses

Cause:

Action:

TCM-00196
Encountered an error while logging out of the imaging system

Category:
Requests/Responses

Cause:

Action:

TCM-00197
Beginning initialization of the Rendering Cache

Category:
Requests/Responses

Cause:

Action:

TCM-00198
Initialization of the Rendering Cache is complete

Category:
Requests/Responses

Cause:

Action:

TCM-00199
WebCenter Content: Imaging API error encountered, attempting restart.

Category:
Requests/Responses

Cause:
A WebCenter Content: Imaging API error was encountered.

Action:
Review the server logs for further information.

TCM-00777
A database error occurred.

Category:
Data

Cause:
An operation caused an unexpected database error.

Action:
Review the logs for the specifics of the database error. You may need to contact Oracle Support Services to resolve the issue.

TCM-00787
A repository error occurred.

Category:
Requests/Responses

Cause:
An unknown error has occurred with a repository.

Action:
Review the logs to determine the cause of the error. You may need to contact Oracle Support Services to resolve the issue.

TCM-00788
The following error is reported by the repository: {0}

Category:
Requests/Responses

Cause:
An error has occurred with a repository. The details of the error were part of the error message.

Action:
Review the message and logs to determine the cause of the error. You may need to contact Oracle Support Services to resolve the issue.

TCM-00789
The Content Server returned no data. This may be an indication of an incorrect server port number, or a connection failure during a request.

Category:
Configuration

Cause:
The Content Server repository returned no data, and it did so without an error. The Content Server was shut down in the middle of a request

Action:
Check the server port used for the connection and make sure it is a correct value. A common mistake is to provide the web server port. The value should match the Content Server IntradocServerPort setting. Check to make sure the Content Server is still up and running.

TCM-00791
The Content Server does not have a defined document profile field.

Category:
Configuration

Cause:
The Content Server repository did not have a defined profile trigger.

Action:
Configure a profile trigger in the Content Server. This can be accomplished by setting EnableIdcProfileField=1 and then restarting the Content Server.

TCM-00792
Your search has timed out. Timeouts are typically a result of searching with value(s) that can be matched by too many documents. Please try refining your search value(s) to narrow the number of documents that will be returned.

Category:
Requests/Responses

Cause:
A timeout error has occurred with a repository.

Action:
The specified query required too much time to complete and timed out while awaiting a response from the database.

TCM-00888
Validation Error.

Category:
Requests/Responses

Cause:
Data supplied to an imaging operation was invalid.

Action:
Correct the invalid data and resend.

TCM-00998
Multiple errors in a subsystem. {0}

Category:
Requests/Responses

Cause:
An error occurred in UOA that has multiple causes.

Action:
Review the logs for the errors. You may need to contact Oracle Support Services to resolve the issue.

TCM-00999
Error in a subsystem. {0}

Category:
Requests/Responses

Cause:
An error occurred in a repository, or when communicating with a workflow server.

Action:
Review the logs for the error. You may need to contact Oracle Support Services to resolve the issue.

TCM-01008
Unable to add application. The application category already exists.

Category:
Requests/Responses

Cause:
A UOA category of the same name already exists.

Action:
Contact Oracle Support Services.

TCM-01009
Unable to add application. The system document category does not exist.

Category:
Requests/Responses

Cause:
A UOA system document category has not been properly configured.

Action:
Ensure that the UOA repository has been initialized prior to creating applications.

TCM-01010
Unable to add application. The application documents folder already exists

Category:
Requests/Responses

Cause:
A UOA folder used for storage of application documents already exists.

Action:
Contact Oracle Support Services.

TCM-01017
Unable to update application. User does not have proper permissions.

Category:
Requests/Responses

Cause:
The current user has not been given the proper rights to update the application.

Action:
Refrain from modifying the application until the proper rights have been granted.

TCM-01018
Unable to delete application. The application contains documents.

Category:
Requests/Responses

Cause:
A user attempted to delete an application that still contains documents.

Action:
Delete all of the documents belonging to the application before attempting to delete the application.

TCM-01019
Another application operation is in progress. Try again later.

Category:
Requests/Responses

Cause:
A user attempted an application operation while another operation was in progress.

Action:
Wait 30 to 60 seconds and try again.

TCM-01020
This document operation is blocked by repository database inconsistencies. This may be due to concurrent application activity (for example, adding, modifying, or deleting an application). Try again later.

Category:
Requests/Responses

Cause:
A user attempted a document operation while the repository metadata table is in an inconsistent state. This could be due to a concurrent application operation.

Action:
Wait 30 to 60 seconds and try again.

TCM-01021
Failed to delete application in the repository. Contact an administrator for assistance.

Category:
Requests/Responses

Cause:
The system was not able to delete the application in the repository.

Action:
Review the logs for possible reasons.

TCM-01025
The NameId for the application does not contain a name or an identifier.

Category:
Requests/Responses

Cause:
The NameId for the application did not contain a name or an identifier.

Action:
Provide either a name or an identifier for the application.

TCM-01027
Lifecycle policy action specification, {0}, is not found.

Category:
Configuration

Cause:
The specified lifecycle policy action specification was not found in the UOA system.

Action:
Ensure that UOA is configured with the specified lifecycle policy action specification.

TCM-01028
Lifecycle policy date rule specification, {0}, is not found.

Category:
Configuration

Cause:
The specified lifecycle policy date rule specification was not found in the UOA system.

Action:
Ensure that UOA is configured with the specified lifecycle policy date rule specification.

TCM-01031
Missing a closing delimiter near "{0}".

Category:
Programmatic

Cause:
An opening delimiter ([) was found without a closing delimiter (]) in a Format Value function.

Action:
Review the Format Value text and ensure that there are matching delimiters.

TCM-01032
The workflow mapping function, {0}, is not a known function.

Category:
Programmatic

Cause:
A workflow Format Value contains a reference to an unknown function.

Action:
Review the API documentation for valid workflow function names.

TCM-01033
The workflow mapping function, {0}, is not allowed.

Category:
Programmatic

Cause:
A workflow function was specified in a location where it is not allowed.

Action:
Review the API documentation for valid workflow function usage.

TCM-01034
The workflow mapping function, {0}, has too many parameters.

Category:
Programmatic

Cause:
Too many parameters were provided for a workflow function.

Action:
Review the API documentation for valid workflow function usage.

TCM-01035
The workflow mapping function, {0}, requires a parameter.

Category:
Programmatic

Cause:
A workflow function was missing a required parameter.

Action:
Review the API documentation for valid workflow function usage.

TCM-01036
The workflow mapping function, {0}, does not accept a parameter.

Category:
Programmatic

Cause:
A parameter was provided to a workflow function that does not accept parameters.

Action:
Review the API documentation for valid workflow function usage.

TCM-01037
Null applications are not allowed.

Category:
Requests/Responses

Cause:
A null value was provided to a function that requires an application definition.

Action:
Provide a valid, non-null, application definition.

TCM-01039
The document is not allowed to be updated. It is read-only.

Category:
Requests/Responses

Cause:
The current user was not given the proper rights to update documents belonging to the application.

Action:
Refrain from modifying the application's documents until the proper rights have been granted.

TCM-02001
The requested document, id={0}, was not found.

Category:
Requests/Responses

Cause:
Document does not exist, or user does not have proper rights.

Action:
Verify document and user rights before attempting to access the document.

TCM-02003
The requested id, {0}, is not a document.

Category:
Requests/Responses

Cause:
Item returned by UOA is not a document.

Action:
Retry action against document.

TCM-02004
The document is currently locked by {0}

Category:
Requests/Responses

Cause:
Document is already locked.

Action:
Unlock document and try again.

TCM-02005
The document cannot be locked

Category:
Requests/Responses

Cause:
Document could not be locked to the user.

Action:
Verify user permissions and try again.

TCM-02006
The document is locked to another user: {0}

Category:
Requests/Responses

Cause:
Document is locked to another user.

Action:
Administrator or current document owner must unlock document.

TCM-02007
The document cannot be unlocked

Category:
Requests/Responses

Cause:
Document could not be unlocked by the user.

Action:
Verify the document state and try to unlock document again.

TCM-02008
The documents cannot be deleted because they are in a legislative hold in the repository.

Category:
Requests/Responses

Cause:
An attempt was made to delete documents that are in legislative hold.

Action:
Refrain from deleting documents until legislative holds have been removed.

TCM-02011
The document is not locked to the requester

Category:
Requests/Responses

Cause:
Document is not locked to the user.

Action:
Document must be unlocked before trying again.

TCM-02012
An invalid file was received "{0}".

Category:
Requests/Responses

Cause:
Invalid file was given to the API.

Action:
Verify the file and try again.

TCM-02014
Original document field values cannot be retrieved.

Category:
Requests/Responses

Cause:
Document fields could not be retrieved from UOA.

Action:
Verify user permissions and try again.

TCM-02015
Invalid field value for field "{0}".

Category:
Requests/Responses

Cause:
Could not resolve field for field value.

Action:
Verify application definition and try again.

TCM-02016
The file name is invalid. A file name must have a file extension, cannot be empty or null, and cannot include any path information.

Category:
Requests/Responses

Cause:
An invalid file name was provided for the document.

Action:
Enter a valid file name. Do not include any path information.

TCM-02019
Replacement or versioning is not allowed for this document.

Category:
Requests/Responses

Cause:
Document cannot be updated.

Action:
Document update is not allowed for documents in this application.

TCM-02020
Page Management functions are valid only with TIFF document types.

Category:
Requests/Responses

Cause:
Cannot modify because it is not a tiff document.

Action:
Page management functions are only valid for tiff documents.

TCM-02021
A page management operation cannot complete because of a system error.

Category:
Requests/Responses

Cause:
Page operation failed. System error occurred accessing image.

Action:
Verify and try again.

TCM-02022
The supporting content key is invalid.

Category:
Requests/Responses

Cause:
Supporting content key for the document is invalid.

Action:
Enter unique supporting content key.

TCM-02023
Cannot find the field {0}, id {1} in the application context.

Category:
Requests/Responses

Cause:
Document missing field information. Cannot create document.

Action:
Enter correct field information.

TCM-02024
Invalid upload token.

Category:
Requests/Responses

Cause:
Token for the uploaded file is invalid.

Action:
Use valid token.

TCM-02025
Cannot move document. Source and destination application are the same.

Category:
Requests/Responses

Cause:
Source and destination applications are the same.

Action:
Specify different application when moving documents.

TCM-02026
The document data provided to the service is invalid

Category:
Requests/Responses

Cause:
Invalid data stream was given to the API

Action:
Check the file and make sure it is valid

TCM-02027
The requested supporting content for the document, id={0}, key={1}, was not found.

Category:
Requests/Responses

Cause:
Supporting content key does not return any results.

Action:
Verify supporting content key is correct.

TCM-02028
This document consists of multiple versions. The destination application does not support versioning.

Category:
Requests/Responses

Cause:
Document consists of multiple versions. Destination application does not support versioning.

Action:
Choose a destination application that supports versioning.

TCM-02029
Write permissions are required on the document in order to set supporting content.

Category:
Requests/Responses

Cause:
Write permissions are required on the document in order to set supporting content.

Action:
Verify user permissions are set correctly for the document

TCM-02030
View permissions are required on the document in order to get supporting content.

Category:
Requests/Responses

Cause:
View permissions are required on the document in order to get supporting content.

Action:
Verify user permissions are set correctly for the document

TCM-02031
Copy failed, document not found.

Category:
Requests/Responses

Cause:
Document does not exist or user does not have rights to copy.

Action:
Verify document and user rights before attempting to copy.

TCM-02032
Moved failed, no document move rights

Category:
Requests/Responses

Cause:
Document does not exist or user does not have rights to move.

Action:
Verify document and user rights before attempting to move.

TCM-02033
Update failed, no document update rights

Category:
Requests/Responses

Cause:
Document does not exist or user does not have rights to update

Action:
Verify document and user rights before attempting to update.

TCM-02034
The document version must be greater than 0.

Category:
Requests/Responses

Cause:
Document version must be greater than 0

Action:
Set version to a value greater than 0

TCM-02035
File, "{0}," is zero length. Documents must have a file length greater than zero.

Category:
Requests/Responses

Cause:
File with zero length was given to the API.

Action:
Check the file and make sure its length is greater than zero.

TCM-02036
Either a valid file, a valid field list, or both, are required to update a document.

Category:
Requests/Responses

Cause:
Invalid file and field list has been passed into update document.

Action:
Verify valid file and field list have been passed in.

TCM-02037
The supporting content key already exists.

Category:
Requests/Responses

Cause:
Supporting content key for the document already exists.

Action:
Enter unique supporting content key.

TCM-02038
The document identifier, {0}, is invalid.

Category:
Requests/Responses

Cause:
The document identifier for the request was invalid.

Action:
Enter a valid document identifier.

TCM-02039
The document action could not be performed because the document is under records management in the repository.

Category:
Requests/Responses

Cause:
A user attempted a document operation while the document is under records management in the repository.

Action:
Refrain from operating or a records managed document.

TCM-02040
The file timeout {0} is invalid for document operations. The timeout must be greater than or equal to 0.

Category:
Requests/Responses

Cause:
The timeout for document operations must be greater than or equal to 0. The current value is invalid

Action:
Set timeout value to greater than or equal to 0.

TCM-03004
Annotation list is Null

Category:
Requests/Responses

Cause:
Annotation list to search is Null.

Action:
Ensure that annotation list object is not null.

TCM-03012
An error occurred while saving annotations

Category:
Requests/Responses

Cause:
An error occurred while saving annotations.

Action:
A repository-specific exception occurred when saving annotations. Check the repository-specific exception stack for diagnostic details.

TCM-03018
Error reading file {0}

Category:
Requests/Responses

Cause:
An error occurred while reading the file

Action:
Check the file and its permissions

TCM-03024
An annotation cannot be accepted due to the lack of permission.

Category:
Requests/Responses

Cause:
An annotation cannot be accepted due to the lack of permission.

Action:
Ensure that all annotations' security settings are compatible with the user's permission set.

TCM-03029
Invalid document Id saving/retrieving document annotations: {0}

Category:
Requests/Responses

Cause:
Invalid document Id when saving/retrieving document annotations.

Action:
Supply a valid document Id.

TCM-03035
User does not have sufficient annotation permission in the destination application.

Category:
Requests/Responses

Cause:
User does not have sufficient annotation permission in the destination application.

Action:
Ensure that the user has sufficient annotation permissions in the destination application for any annotations to be applied.

TCM-03036
An error occurred retrieving annotations for the document.

Category:
Requests/Responses

Cause:
Annotations for the specified document could not be retrieved.

Action:
A repository-specific exception occurred when saving annotations. Check the repository-specific exception stack for diagnostic details.

TCM-03037
Error saving annotations to a document version that is not the current version.

Category:
Requests/Responses

Cause:
An attempt was made to save annotations to a document version that is not the current version.

Action:
Annotations cannot be saved to previous versions of a document.

TCM-04001
A valid Input name or ID must be specified for the operation to complete.

Category:
Requests/Responses

Cause:
The requested Name and ID of the input to be deleted is invalid.

Action:
Provide a valid Name or ID for the Input to delete

TCM-04002
No Input definitions found for the input name {0}, ID {1}.

Category:
Requests/Responses

Cause:
The specified Input could not be found in the system.

Action:
Recheck the Input name or ID.

TCM-04003
Multiple Input definitions found for input name {0}, ID {1}.

Category:
Requests/Responses

Cause:
The name or ID provided has multiple Input Definitions associated with it.

Action:
Examine the system for data integrity.

TCM-04004
Input name is empty

Category:
Requests/Responses

Cause:
The name of the Input is invalid

Action:
Make sure the Input name is not missing, blank or only strings

TCM-04005
Invalid Input properties

Category:
Requests/Responses

Cause:
The properties section of the Input Definition was invalid.

Action:
Make sure that the Input properties section is not missing.

TCM-04006
Input source must be set

Category:
Requests/Responses

Cause:
The Input Definition is missing the input source

Action:
Provide a valid input source

TCM-04008
The Input's Source Properties section is invalid

Category:
Requests/Responses

Cause:
The Input Source Properties section of the Input definition is invalid.

Action:
Check to make sure the properties are set and have valid values.

TCM-04009
The specified data source is invalid.

Category:
Requests/Responses

Cause:
The Data Source in the Input Source Properties was invalid.

Action:
Make sure that the data source is specified and has a valid value.

TCM-04010
The Input Source in the definition is invalid

Category:
Requests/Responses

Cause:
The Input Source is invalid.

Action:
Check the Input Source and make sure it's valid.

TCM-04012
The Input does not define any mappings, or one or more mappings are invalid

Category:
Requests/Responses

Cause:
The Input Mappings section of the Input definition is invalid.

Action:
Check to make sure mappings have been set and map between valid fields.

TCM-04013
The provided StateUpdates are invalid.

Category:
Requests/Responses

Cause:
No valid values were provided for updating the input's state.

Action:
Ensure that the Input.StateFlags provided for all updates are valid.

TCM-04014
The specified input's state cannot be updated

Category:
Requests/Responses

Cause:
Updating the current state for the specified input failed.

Action:
Ensure that the specified input exists, and that the new state settings are valid.

TCM-04015
The specified input definition cannot be updated

Category:
Requests/Responses

Cause:
Updating the provided sections of the input definition failed.

Action:
Ensure values have been properly provided for all of the definition sections you are attempting to update

TCM-04016
The provided Input object is null

Category:
Requests/Responses

Cause:
The Input object provided is null.

Action:
Provide a valid Input, with appropriate sections completed.

TCM-04017
Cannot find the configuration file for the local Input Server settings.

Category:
Requests/Responses

Cause:
The configuration file specified could not be found.

Action:
Ensure that the specified file exists, and that the user has the correct permissions

TCM-04018
An error was encountered loading the configuration file

Category:
Requests/Responses

Cause:
The configuration file couldn't be opened.

Action:
Ensure that the specified file exists, and that the user has the correct permissions

TCM-04019
Failed to get the Input Source list

Category:
Requests/Responses

Cause:
Could not get a listing of available Input Sources

Action:
Check the jar configuration files and make sure they are defined correctly

TCM-04020
The Input Path for CSV filings has not been configured properly.

Category:
Requests/Responses

Cause:
The Input Path is missing from the CSV configuration file.

Action:
Check the CSV configuration file to make sure it exists and is correct.

TCM-04021
Input Source {0} cannot be found

Category:
Requests/Responses

Cause:
The requested Input Source was not found

Action:
Check the /META-INF/input-agent-config.properties file of Input Source jar and make sure it's correct.

TCM-04022
Error loading Input Source Plugin

Category:
Requests/Responses

Cause:
An error occurred while trying to load the input source

Action:
Check the class path to make sure the input source can be loaded.

TCM-04023
The stage path cannot be initialized for processing

Category:
Requests/Responses

Cause:
The stage directory could not be initialized.

Action:
Check the permissions to the Input Directory.

TCM-04024
The file {0} cannot be moved to the directory {1}

Category:
Requests/Responses

Cause:
The input file could not be properly staged for processing.

Action:
Check the input file and stage path for proper permissions.

TCM-04025
the configuration folder path cannot be found

Category:
Requests/Responses

Cause:
The configuration file wasn't found

Action:
Make sure all the configuration files are in place and are correct.

TCM-04027
One or more of the Input Fields are mapped to multiple Application or system fields

Category:
Requests/Responses

Cause:
One of the input mappings is assigned to multiple locations.

Action:
Remove all duplicate mappings from the definition

TCM-04028
The requested input field isn't mapped to an application field

Category:
Requests/Responses

Cause:
The requested mapping wasn't found in the index

Action:
Pass in the correct input field name

TCM-04029
The parser has not been initialized, call StartFiling

Category:
Requests/Responses

Cause:
Start Filing wasn't called on the parser

Action:
Call start filing

TCM-04030
The input file cannot be properly closed

Category:
Requests/Responses

Cause:
A file error closing the input file

Action:
Check file permissions and input file

TCM-04032
The specified data range is invalid

Category:
Requests/Responses

Cause:
Start and end positions for examining the data source are invalid

Action:
Request a valid range

TCM-04033
Date value does not conform to the short, medium or long format type for the current locale, date cannot be parsed.

Category:
Requests/Responses

Cause:
Date format does not parse to a valid date

Action:
Pass in a date value that conforms to the locales short, medium or long format

TCM-04034
Cannot get the local machine name

Category:
Requests/Responses

Cause:
The host could not be determined.

Action:
Check the error code.

TCM-04035
Application {0}({1}) cannot be found. Verify that the application exists and you have permissions to it.

Category:
Requests/Responses

Cause:
The application that the mapping is pointing to could not be found

Action:
Check to make sure that you have access to that Application or that the Application is still valid.

TCM-04036
The mapping for input section {0} is invalid

Category:
Requests/Responses

Cause:
The application field specified in the Input mapping is invalid.

Action:
Check to make sure that the specified application field ID is set and exists in the target application

TCM-04038
Application "{0}" cannot be loaded. Verify that the application exists and you have permissions to it.

Category:
Requests/Responses

Cause:
The Application specified could not be loaded

Action:
Check to make sure that the Application exists and you have access to it.

TCM-04039
The Sample Path for CSV filings has not been configured correctly.

Category:
Requests/Responses

Cause:
The sample path is not configured correctly

Action:
Make sure the sample path configuration value is set to a valid location

TCM-04040
The sample path {0} cannot be initialized for processing

Category:
Requests/Responses

Cause:
The sample path could not be created

Action:
Make sure the sample path is valid, accessible by the server and has the correct permissions

TCM-04041
The get contents request for data source {0} cannot be processed because it is not a sample source.

Category:
Requests/Responses

Cause:
User attempted to get sample data for a data source that wasn't a sample source.

Action:
Use only sample sources when requesting source contents.

TCM-04045
The Input {0} has {1} unfinished batches open against it and cannot be deleted

Category:
Requests/Responses

Cause:
There is an open batch against the Input

Action:
Wait for the filing to finish before deleting the Input

TCM-04046
Input {0} has active or pending jobs and cannot be deleted

Category:
Requests/Responses

Cause:
There are queued jobs for the Input

Action:
Wait for all the work to finish before deleting the Input

TCM-04047
The Input Agent service cannot be accessed to process commands.

Category:
Requests/Responses

Cause:
The Input Agent could not be found to communicate with.

Action:
Validate that the Imaging.ear is started and running properly.

TCM-04048
Content cannot be read from the data source {0}

Category:
Requests/Responses

Cause:
The data source content could not be read

Action:
Examine the inner exception for more information

TCM-04049
The StateUpdate value passed to the ModifyState call is invalid

Category:
Requests/Responses

Cause:
The state update object passed to the API request is invalid

Action:
Check the StateUpdate object to make sure it's properly formed

TCM-04050
No Application is specified in the Input Mapping section

Category:
Requests/Responses

Cause:
The input definition does not have the destination application id set

Action:
Set the Application Id in the Input mapping section

TCM-04051
The input file locale has already been set and cannot be changed

Category:
Requests/Responses

Cause:
A locale has already been specified for the input file and cannot be changed

Action:
Remove the extra locale command from the input file

TCM-04052
The locale identifier {0} is not a valid locale identifier

Category:
Requests/Responses

Cause:
The locale parameter specified in the locale command is invalid

Action:
Specify a valid locale

TCM-04053
The locale command can only be used at the beginning of the input file

Category:
Requests/Responses

Cause:
The locale command was used after the start of the file

Action:
Only use the locale command at the top of the input file

TCM-04054
The start position {0} or range {1} specified are invalid. Make sure that the start position and range values are positive and that the range is greater than the start.

Category:
Requests/Responses

Cause:
The start position or range values are invalid.

Action:
Examine the calling code and ensure that the start position and range are greater than 0 and that the range is greater than the start position

TCM-04055
The value {0} provided for the Input Server state update is the wrong type or is out of range.

Category:
Requests/Responses

Cause:
The value provided to the StateFlag request was invalid.

Action:
Check to make sure the correct type has been passed for the StateFlag and that the value is in the correct range.

TCM-05003
The UOA Repository search failed

Category:
Requests/Responses

Cause:
No Search was found matching the selected search id

Action:
Re-list the available searches

TCM-05004
The Search Definition supplied was null

Category:
Requests/Responses

Cause:
A null value was provided for the search.

Action:
Provide a non-null search.

TCM-05005
The Search Name supplied was null or empty

Category:
Requests/Responses

Cause:
Search name was null or empty

Action:
Provide a valid search name.

TCM-05006
The search supplied has a results formatting structure that is null.

Category:
Requests/Responses

Cause:
The search formatting structure was null or empty.

Action:
Provide a valid search formatting structure.

TCM-05007
The requested search, {0}, was not found.

Category:
Requests/Responses

Cause:
The search requested does not exist. The user does not have access to the search.

Action:
Check the requested search name or ID for correctness. Check the user's access to the requested search.

TCM-05009
A required search parameter, {0}, was missing.

Category:
Requests/Responses

Cause:
A required parameter was missing for this search

Action:
Resubmit the search with the required parameter(s).

TCM-05012
Invalid operator used in search parameter

Category:
Requests/Responses

Cause:
An invalid operator was used in the search parameter

Action:
Use an operator defined in the operator picklist.

TCM-05013
A Search Argument was provided that was not defined in the search

Category:
Requests/Responses

Cause:
A search argument was provided that was not defined in the search

Action:
Provide only those arguments defined in the search.

TCM-05014
The search argument contains a value for a read-only parameter

Category:
Requests/Responses

Cause:
A search argument was provided containing a value for a read-only parameter

Action:
Remove the read only parameter from the search arguments.

TCM-05015
There are multiple search arguments for a single parameter.

Category:
Requests/Responses

Cause:
Multiple search arguments were provided for a single parameter.

Action:
Verify that the number of the search arguments matches the number of parameters.

TCM-05016
The type for the search argument does not match the search parameter type.

Category:
Requests/Responses

Cause:
A search argument with an incorrect type was provided for a search parameter.

Action:
Use an argument with a type that matches the search parameter type.

TCM-05017
The entered value, {0}, is < 1. The default maximum rows returned value must be >= 1.

Category:
Requests/Responses

Cause:
A value less than 1 was entered for the defalut value for the maximum number of rows to be returned from a search.

Action:
Use a value that is greater than or equal to 1.

TCM-05018
The entered value, {0}, is invalid for panel placement. Enter 1, 2, or 3.

Category:
Requests/Responses

Cause:
An invalid value is entered for placement of a panel.

Action:
Enter 1, 2, or 3

TCM-05019
Entered value, {0}, for zoom level in not valid, is < 1. Pick values from 1,2,3,20,50,100,150,200.

Category:
Requests/Responses

Cause:
An invalid value is entered for zoom level.

Action:
Pick values from 1,2,3,20,50,100,150,200.

TCM-06001
Unable to retrieve Role: {0}

Category:
Requests/Responses

Cause:
The role specified was not found.

Action:
Add the role to the security provider or use a defined role.

TCM-06002
Access is denied.

Category:
Requests/Responses

Cause:
User does not have access to the requested information.

Action:
Update the user's permissions.

TCM-06004
Unable to locate the security member specified.

Category:
Requests/Responses

Cause:
The security member does not exist.

Action:
Add the security member to the security provider.

TCM-06009
Unable to locate the system group: {0}

Category:
Requests/Responses

Cause:
The specific system group was not found.

Action:
Add the system group using the security provider.

TCM-06010
Agent users are only allowed to log in through the agent services.

Category:
Requests/Responses

Cause:
An agent user was used to attempt a log in.

Action:
Log in using a different user.

TCM-06011
Users assigned the 'admin' group either directly or indirectly are not allowed to log into WebCenter Content: Imaging.

Category:
Requests/Responses

Cause:
Users assigned the 'admin' group are not allowed to log in because the repository attaches special meaning to this group.

Action:
Log in using a different user or remove the 'admin' group association with this user.

TCM-06012
The User {0} does not exist in the policy store.

Category:
Requests/Responses

Cause:
The security provider was unable to locate the user specified.

Action:
Enter the user into the security provider.

TCM-06013
Unable to locate the default policy store.

Category:
Requests/Responses

Cause:
Unable to load the policy store.

Action:
The default policy store has not been configured correctly.

TCM-06014
The user's principal does not contain a subject.

Category:
Requests/Responses

Cause:
The principal object was not found in the user token.

Action:
Make sure the principal exists within the user token.

TCM-06015
The Group {0} does not exist in the policy store.

Category:
Requests/Responses

Cause:
The authentication provider was unable to locate the group specified.

Action:
Enter the group into the authentication provider.

TCM-06016
Access to modify the security of this definition is denied.

Category:
Requests/Responses

Cause:
The user was unable to modify the security of this definition.

Action:
Update the user permissions with the modify permission.

TCM-06017
Access to modify the document security of this definition is denied.

Category:
Requests/Responses

Cause:
The user was unable to modify the document security of this definition.

Action:
Update the user permissions to include the modify document security permission.

TCM-06018
Unable to create resource in policy store for: {0}

Category:
Requests/Responses

Cause:
Unable to create resource in policy store for: {0}

Action:
The default policy store has not been configured correctly.

TCM-06019
Bad principal type returned by Policy Store for "{0}": {1}

Category:
Requests/Responses

Cause:
Bad principal type returned by Policy Store for "{0}": {1}

Action:
The default policy store has not been configured correctly.

TCM-06020
No Security Profile was found during system startup.

Category:
Requests/Responses

Cause:
No Security Profile was found during system startup.

Action:
The system has not been configured correctly to use a security profile.

TCM-06021
The Security Profile failed to initialize during system startup: {0}

Category:
Requests/Responses

Cause:
The Security Profile failed to initialize during system startup: {0}

Action:
The system has not been configured correctly to use the security profile.

TCM-07001
Requested output format does not support multiple pages

Category:
Requests/Responses

Cause:
An output format was requested that does not support multiple pages.

Action:
Choose a different output format, or restrict the output request to a single page.

TCM-07002
Invalid Document reference in render request

Category:
Requests/Responses

Cause:
The supplied documentObject parameter is null

Action:
Provide a valid Document object reference when calling RenderManager.render().

TCM-07003
Invalid input stream in render request

Category:
Requests/Responses

Cause:
The supplied sourceStream parameter is null

Action:
Provide a valid InputStream object reference when calling RenderManager.render().

TCM-07004
No render options in render request

Category:
Requests/Responses

Cause:
The supplied options parameter is null

Action:
Provide a valid RenderOptions object reference when calling RenderManager.render().

TCM-07008
This document contains annotations that prevent the user from accessing this document in its raw format

Category:
Requests/Responses

Cause:
This document contains annotations that prevent the user from accessing this document in its raw format.

Action:
Export to TIFF with the annotations burned in or contact your administrator for access to the native format.

TCM-07009
The mime-type of "{0}" is not supported.

Category:
Requests/Responses

Cause:
An unsupported mime-type was requested.

Action:
Correct the document content (mime) type.

TCM-07011
An I/O error occurred during image translation.

Category:
Requests/Responses

Cause:
An I/O error occurred during image translation.

Action:
Check permissions and free space in the server temp directory.

TCM-07012
An error occurred when loading an image for translation.

Category:
Requests/Responses

Cause:
An error occurred when loading an image for translation.

Action:
Image handling components failed to load the image. Check nested exception details for diagnostic information.

TCM-07013
There was an error reading TIFF headers. The file may be corrupt.

Category:
Requests/Responses

Cause:
There was an error reading TIFF headers. The file may be corrupt.

Action:
Check permissions and free space in the server temp directory.

TCM-07014
An error occurred when processing image manipulation commands during save.

Category:
Requests/Responses

Cause:
An error occurred when processing image manipulation commands during save.

Action:
Image handling components failed to load the image. Check nested exception details for diagnostic information.

TCM-07016
An I/O error occurred creating the output for this request.

Category:
Requests/Responses

Cause:
An I/O error occurred creating the output for this request.

Action:
Check for nested exceptions, permissions and free space in the server temp directory.

TCM-07017
No document specified when burning annotations into image

Category:
Requests/Responses

Cause:
No document specified when burning annotations into image.

Action:
Specify a valid document path to the document source.

TCM-07019
The requested scale is not within the allowed value range; {0}-{1}

Category:
Requests/Responses

Cause:
The requested scale is not within the allowed value range.

Action:
Provide a scale factor value within the supported range.

TCM-07020
The requested fit rectangle is empty

Category:
Requests/Responses

Cause:
The requested fit rectangle cannot be empty.

Action:
Provide a non-null, non-empty rectangle.

TCM-07021
Unable to get annotation permissions from document

Category:
Requests/Responses

Cause:
Annotation permissions could not be determined.

Action:
Contact the system administrator.

TCM-07022
The supplied document object is null

Category:
Requests/Responses

Cause:
The cache was given a null document object.

Action:
Contact the system administrator.

TCM-07023
A cache exception occurred. {0}

Category:
Requests/Responses

Cause:
A RenderPageCache exception occurred: {0}

Action:
Check the cache exception code and nested exception details for diagnostic information.

TCM-07024
A RenderPageCache object was not found

Category:
Requests/Responses

Cause:
An error occurred retrieving an object from the cache.

Action:
Check the directory and nested exception details for diagnostic information.

TCM-07025
Page number must be a positive value.

Category:
Requests/Responses

Cause:
Page number must be a positive value.

Action:
Provide page number values greater than zero.

TCM-07026
Bounding rectangle specified is empty.

Category:
Requests/Responses

Cause:
Bounding rectangle specified is empty.

Action:
Provide a non-empty rectangle definition.

TCM-07027
The supplied outputType parameter is null.

Category:
Requests/Responses

Cause:
The supplied outputType parameter is null.

Action:
Provide a value for the outputType parameter.

TCM-07028
An invalid argument was provided to method {0}({1}).

Category:
Requests/Responses

Cause:
An invalid argument was provided to a method call.

Action:
Provide non-null values. Page specifications must be > 0.

TCM-07029
Cannot burn the annotations into the destination file {0}.

Category:
Requests/Responses

Cause:
An error occurred while burning annotations into the destination tiff.

Action:
Check the embedded exception for the specific cause of the error.

TCM-07030
An invalid path was specified. Provide a non-null, non-empty string or an existing directory path.

Category:
Requests/Responses

Cause:
An invalid path was set for the render CacheLocation.

Action:
Provide an empty value or an existing directory path.

TCM-07031
An invalid value was specified. Check spelling and character case.

Category:
Requests/Responses

Cause:
An invalid value was specified.

Action:
Check spelling and character case.

TCM-07033
An invalid value was specified. Enter a value from 0 to 100.

Category:
Requests/Responses

Cause:
An invalid value was specified.

Action:
Enter a value from 0 to 100.

TCM-07036
An error occurred during document translation.

Category:
Requests/Responses

Cause:
An error occurred during document translation.

Action:
Check nested exception details for diagnostic information.

TCM-07037
An error occurred retrieving a rendition to create a copy with.

Category:
Requests/Responses

Cause:
An error occurred retrieving a rendition to create a copy with.

Action:
The rendering system was unable to generate a rendition of the document. Check the nested exception details for diagnostic information.

TCM-07038
The requested page number is beyond the document page range.

Category:
Requests/Responses

Cause:
The requested page number is beyond the document page range.

Action:
Specify a valid page number that is within the range of document pages.

TCM-07039
This document content is sealed. IRM content cannot be rendered.

Category:
Requests/Responses

Cause:
This document content is sealed. IRM content cannot be rendered.

Action:
Download the native document and use Oracle IRM Desktop to access this file content.

TCM-07040
RenderAgent is not initialized. Requests cannot be processed.

Category:
Requests/Responses

Cause:
RenderAgent is not initialized. Requests cannot be processed.

Action:
RenderAgentBean initialization failed. Check the nested exception details for diagnostic information.

TCM-07041
The specified viewer cache days value of {0} is invalid. The number of days must be greater than or equal to 0 and less than or equal to 30.

Category:
Requests/Responses

Cause:
The cache days value that was given is invalid.

Action:
Check the cache days parameter sent to the MBean is in the valid range of 0-30.

TCM-07042
The credential for storing the encryption key was not found. It must exist prior to enabling viewer cache encryption.

Category:
Requests/Responses

Cause:
The credential for storing the encryption key was not found.

Action:
Verify the credential exists prior to turning on cache encryption.

TCM-07043
An error occurred while queuing the cache request. The Oracle WebCenter Content: Imaging Viewer Cache application (imaging-vc) was not found.

Category:
Requests/Responses

Cause:
The viewer cache application deployment was not found.

Action:
Check the domain configuration an verify that the viewer cache application is properly deployed.

TCM-08001
System folder "{0}" is not found

Category:
Installation

Cause:
A UOA system folder was not found.

Action:
Ensure proper UOA system installation.

TCM-08005
User does not have create permissions.

Category:
Requests/Responses

Cause:
An attempt was made to create documents in an application where the user does not have create permission.

Action:
Ensure user is granted create permission or refrains from creating documents.

TCM-08006
User does not have delete permissions.

Category:
Requests/Responses

Cause:
An attempt was made to delete documents in an application where the user does not have delete permission.

Action:
Ensure user is granted delete permission or refrains from deleting documents.

TCM-08008
User does not have permission to access the "{0}" system folder.

Category:
Requests/Responses

Cause:
An attempt was made to access a system folder, but the user does not have the proper permission.

Action:
Ensure user is granted the proper permission or refrains from accessing the folder

TCM-08009
Workspace "{0}" is not found.

Category:
Installation

Cause:
A workspace in UOA was not found.

Action:
Ensure proper UOA system installation.

TCM-08010
Interrupted during login retry. Stopping further login attempts.

Category:
Requests/Responses

Cause:
An agent thread was interrupted while attempting to log in.

Action:
Check to see if the thread was shut down.

TCM-08011
Unable to log in to the WebCenter Content: Imaging system

Category:
Requests/Responses

Cause:
An error was encountered while logging in to the imaging system.

Action:
Check the imaging logs and any inner exception for details on why the login failed.

TCM-09010
An error occurred trying to list storage policy volumes.

Category:
Requests/Responses

Cause:
An error occurred trying to obtain a list of storage volumes from a repository.

Action:
Ensure that the repository is running and functioning correctly.

TCM-09011
An error occurred trying to determine the default storage policy volume.

Category:
Requests/Responses

Cause:
An error occurred trying to determine the default volume for a repository.

Action:
Ensure that the repository is running and functioning correctly.

TCM-09012
An error occurred trying to list retention policies.

Category:
Requests/Responses

Cause:
An error occurred trying to list retention policies for a repository.

Action:
Ensure that the repository is running and functioning correctly.

TCM-09013
An error occurred trying to validate a volume.

Category:
Requests/Responses

Cause:
An error occurred trying to validate a volume for a repository.

Action:
Ensure that the repository is running and functioning correctly.

TCM-09014
An error occurred trying to validate a storage group.

Category:
Requests/Responses

Cause:
An error occurred trying to validate a storage group for a repository.

Action:
Ensure that the repository is running and functioning correctly.

TCM-09015
An error occurred trying to validate a retention policy.

Category:
Requests/Responses

Cause:
An error occurred trying to validate a retention policy for a repository.

Action:
Ensure that the repository is running and functioning correctly.

TCM-09016
An error occurred trying to find a retention policy.

Category:
Requests/Responses

Cause:
An error occurred trying to find a retention policy in a repository.

Action:
Ensure that the repository is running and functioning correctly.

TCM-09017
An error occurred trying to discover lifecycle policies.

Category:
Requests/Responses

Cause:
An error occurred trying to find lifecycle policies in a UOA repository.

Action:
Ensure that UOA is running and functioning correctly.

TCM-09018
An error occurred trying to create a storage policy.

Category:
Requests/Responses

Cause:
An error occurred trying to create a storage policy in a UOA repository.

Action:
Ensure that UOA is running and functioning correctly.

TCM-09019
An error occurred trying to delete a storage policy.

Category:
Requests/Responses

Cause:
An error occurred trying to delete a storage policy in a UOA repository.

Action:
Ensure that UOA is running and functioning correctly.

TCM-09020
An error occurred trying to load action specifications.

Category:
Requests/Responses

Cause:
An error occurred trying to load action specifications in a UOA repository.

Action:
Ensure that UOA is running and functioning correctly.

TCM-09021
An error occurred trying to load date rule specifications.

Category:
Requests/Responses

Cause:
An error occurred trying to load date rule specifications in a UOA repository.

Action:
Ensure that UOA is running and functioning correctly.

TCM-09030
Error connecting to workflow system.

Category:
Requests/Responses

Cause:
An error occurred trying to connect to a workflow server.

Action:
Ensure that the workflow server is running and functioning correctly.

TCM-09032
Error determining workflow composite services. The composite DN is {0}.

Category:
Requests/Responses

Cause:
An error occurred trying to determine services for a composite.

Action:
Ensure that the workflow server is running and functioning correctly.

TCM-09033
Error getting workflow system components.

Category:
Requests/Responses

Cause:
An error occurred trying to determine components for a workflow server.

Action:
Ensure that the workflow server is running and functioning correctly.

TCM-09034
Error reading workflow service WSDL document {0}

Category:
Requests/Responses

Cause:
An error occurred trying to read the workflow service WSDL document.

Action:
Ensure that the workflow server is running and functioning correctly. If WSDL protocol is HTTPS, ensure SSL configurations for both imaging and workflow server are correct.

TCM-09035
Error accessing credential key "{0}"

Category:
Requests/Responses

Cause:
An error occurred access a credential key in the credential store.

Action:
Ensure that the correct key was provided and the credentials are properly configured in the credential store.

TCM-09036
Unsupported workflow service. Service definition exceeds hierarchical depth of {0}.

Category:
Requests/Responses

Cause:
Workflow service Definition exceeded the maximum hierarchical depth given in the error message.

Action:
Select a different workflow service operation.

TCM-09037
Unsupported workflow service. Service definition contains choice elements.

Category:
Requests/Responses

Cause:
Workflow service definition contains unsupported choice elements.

Action:
Select a different workflow service operation.

TCM-09038
Unable to map one or more values to workflow payload nodes for document {0}. The missing nodes are: {1}.

Category:
Requests/Responses

Cause:
Workflow payload may have changed after worflow was configured.

Action:
Reconfigure the workflow.

TCM-09040
Unable to obtain a Subject that is required to enable sending tenant information to a workflow server.

Category:
Requests/Responses

Cause:
No Subject was found or created.

Action:
Contact your system administrator and review the server logs for any related information.

TCM-09041
Unable to obtain an ApplSession that is required to enable sending tenant information to a workflow server.

Category:
Requests/Responses

Cause:
No ApplSession was created.

Action:
Contact your system administrator and review the server logs for any related information.

TCM-09042
Unable to find the required libraries to create an ApplSession.

Category:
Requests/Responses

Cause:
The required Appl Core libraries could not be found.

Action:
Contact your system administrator and review the server's deployment libraries.

TCM-09043
The ImagingTenant configuration setting is empty or has a bad value.

Category:
Requests/Responses

Cause:
The ImagingTenant configuration setting is empty or has a bad value.

Action:
Set the ImagingTenant configuration setting to a valid tenant identifier.

TCM-09044
There is no user name configured to create an ApplSession.

Category:
Requests/Responses

Cause:
There is no user name configured to create an ApplSession.

Action:
Change the application workflow configuration to set a csf.key.

TCM-09045
There is no csf.key mapping in an application's workflow configuration.

Category:
Requests/Responses

Cause:
There is no csf.key mapping in an application's workflow configuration.

Action:
Change the application workflow configuration to set a csf.key.

TCM-10001
An error was encountered while searching the repository for closed batches

Category:
Requests/Responses

Cause:
An error occurred while searching the CDB repository for closed batches

Action:
Check the associated exception and CDB log files for errors

TCM-10002
Batch ID {0} for Application {1} has been closed and cannot be indexed into, operation aborted

Category:
Requests/Responses

Cause:
The user requested to index a document into a batch that has been closed

Action:
Check the calling code to determine why the batch was committed too early

TCM-10003
Batch ID {0} for Application {1} has already been committed

Category:
Requests/Responses

Cause:
The user attempted to commit a batch that was already closed

Action:
Check the calling code to determine why the batch was committed twice

TCM-10004
No Batches found for the Batch Name {0}, ID {1}.

Category:
Requests/Responses

Cause:
The Batch could not be found in the CDB system

Action:
Check the NameId passed to the API and make sure it exists

TCM-10005
The target application specified in the Batch object is invalid

Category:
Requests/Responses

Cause:
The target application specified in the Batch object is invalid

Action:
Check the Batch object and ensure that the target application is valid

TCM-10006
No Batches found for Batch ID {0}

Category:
Requests/Responses

Cause:
The Batch could not be found in the CDB system

Action:
Check the NameId passed to the API and make sure it exists

TCM-10007
The Batch provided is null

Category:
Requests/Responses

Cause:
The specified Batch is null

Action:
Pass a valid Batch object to the API call

TCM-10008
The requested Batch ID {0} has documents indexed into it and cannot be removed.

Category:
Requests/Responses

Cause:
The requested batch could not be deleted because it had documents indexed to it.

Action:
Double check that the correct batch was requested and verify that it is empty.

TCM-11001
Turning on or off the auditing configuration failed

Category:
Requests/Responses

Cause:
An FDK Exception was generated by the UOA system when attempting to set the auditing configuration.

Action:
Correct the underlying UOA repository configuration.

TCM-11002
The search of the audit history failed.

Category:
Requests/Responses

Cause:
The search of the repository for auditing data resulted in a repository exception.

Action:
Correct the error identified in the underlying repository exception.

TCM-14000
The provided URL ticket is invalid.

Category:
Requests/Responses

Cause:
The provided URL ticket was determined to be invalid.

Action:
Pass a valid ticket to the API call.

TCM-14001
The URL ticket is set to expire but does not have an expiration time set.

Category:
Requests/Responses

Cause:
The URL ticket was set to expire, but did not have an expiration time set.

Action:
Turn off the expiration or set the expiration time for the ticket.

TCM-14002
No parameters exist in the provided URL ticket.

Category:
Requests/Responses

Cause:
No parameters were specified in the URL ticket.

Action:
Add at least 1 parameter to the URL ticket.

TCM-14003
The parameter for value {0} in the URL ticket is missing a name.

Category:
Requests/Responses

Cause:
The ticket parameter did not have a name defined.

Action:
Assign a name to the ticket parameter.

TCM-14004
The parameter {0} does not have a value assigned to it.

Category:
Requests/Responses

Cause:
Ticket parameter did not have a value defined.

Action:
Assign a value to the parameter.

TCM-14005
The provided ticket identifier is invalid.

Category:
Requests/Responses

Cause:
The ticket identifier was invalid.

Action:
Specify a valid ticket identifier.

TCM-14006
A ticket with the identifier {0} cannot be found.

Category:
Requests/Responses

Cause:
The provided ticket identifier could not be found in the system.

Action:
Verify that the ticket identifier is correct.

TCM-14007
The ticket agent is not processing requests.

Category:
Requests/Responses

Cause:
The ticket agent service could not be located.

Action:
Verify that the imaging ear deployment is valid and is running.

TCM-14008
A create ticket request that is set to expire has an invalid expiration date.

Category:
Requests/Responses

Cause:
An attempt was made to create a ticket with an expiration date in the past.

Action:
Fix the create request so that the ticket has a date in the future.

TCM-14009
The ticket parameter name {0} is longer than the maximum allowed name length of 200.

Category:
Requests/Responses

Cause:
An attempt was made to create a ticket parameter with a name that is too long.

Action:
Shorten the parameter name to be less than 200 characters.

TCM-14010
The ticket parameter value {0} is longer than the maximum allowed value length of 200.

Category:
Requests/Responses

Cause:
An attempt was made to create a ticket parameter with a value that is too long.

Action:
Shorten the parameter value to be less than 200 characters.

TCM-15000
The provided Connection object is null

Category:
Requests/Responses

Cause:
No Connection was provided

Action:
Call the method with a valid Connection object

TCM-15001
Failed to remove the connection as it has the following application dependencies: {0}.

Category:
Requests/Responses

Cause:
Connection is still in use

Action:
Remove the dependent applications prior to removing the connection

TCM-15002
Attempting to create or modify a connection with the following details: {0}.

Category:
Requests/Responses

Cause:

Action:

TCM-15003
Connection successfully created or modified.

Category:
Requests/Responses

Cause:

Action:

TCM-15004
An error occurred during an attempt to create or modify a connection. {0}.

Category:
Requests/Responses

Cause:
An error occurred creating a connection.

Action:
See the log for details of the error and correct the problem before trying again.

TCM-16001
The import data supplied is null.

Category:
Requests/Responses

Cause:
Data supplied for the import operation was null.

Action:
Verify the import data is valid and not null.

TCM-16002
Import/Export requires administrator privileges in order to run.

Category:
Requests/Responses

Cause:
The user supplied does not have the proper permissions.

Action:
Verify the user is an administrator.

TCM-70007
The specified Input Source {0} cannot be found.

Category:
Requests/Responses

Cause:
An Input Source name was provided that does not match any sources that the Input Server has loaded.

Action:
Check the Input Source name.

TCM-70008
The server interval setting is missing from the configuration file.

Category:
Requests/Responses

Cause:
The server interval configuration is missing from the configuration file.

Action:
Check the configuration file.

TCM-70009
The Input Definition is invalid.

Category:
Requests/Responses

Cause:
The Input parameter was null.

Action:
Supply a valid Input to the call.

TCM-70010
No data was provided for the mapped document file section.

Category:
Requests/Responses

Cause:
A document file was not provided.

Action:
Add a patch to the desired document image file to the input file.

TCM-70013
Cannot find the field {0}, id {1} in the Application, check the Application and Input for proper mappings.

Category:
Requests/Responses

Cause:
The application field for a section mapping couldn't be found

Action:
Check to make sure the application field hasn't been deleted and examine the Input field mappings

TCM-70015
The Batch {0} given to Input Agent is marked closed and cannot be used to add objects to.

Category:
Requests/Responses

Cause:
The Batch that Input Agent was assigned to file to is marked as closed

Action:
Restart the entire input file as a new filing.

TCM-70016
A check interval setting of {0} is invalid. Specify a value between 1 and 60.

Category:
Requests/Responses

Cause:
An invalid check interval was provided.

Action:
Set the interval between 1 and 60.

TCM-70017
An error occurred while manipulating the Input Filing Queue

Category:
Requests/Responses

Cause:
An error occurred while trying to browse the input queue

Action:
Check the embedded error for more details

TCM-70018
The value {0} is too large or small to fit in a numeric field.

Category:
Requests/Responses

Cause:
The value that was parsed was outside the valid range for a numeric type.

Action:
Fix the value so that it is inside the numeric data type range.

TCM-70020
The retry count setting {0} is invalid, enter a value between 1 and 100

Category:
Requests/Responses

Cause:
An invalid retry count was set into the MBean

Action:
Try using a retry value between 1 and 100

TCM-70021
The input value {0} could not be converted to a date. It does not conform to a short, medium or long date format for the current locale.

Category:
Requests/Responses

Cause:
An invalid date string was parsed from the input file

Action:
Correct the value so that it is in the correct date format

TCM-70022
The input value {0} could not be converted to a number.

Category:
Requests/Responses

Cause:
An invalid decimal string was parsed from the input file

Action:
Correct the value so that it is a valid number

TCM-70023
The input value {0} could not be converted to a decimal.

Category:
Requests/Responses

Cause:
An invalid date string was parsed from the input file

Action:
Correct the value so that it is a valid decimal

TCM-70024
An existing set of state information was found for the job {0} for Input {1} and cannot be duplicated. Input Agent is ignoring this request.

Category:
Requests/Responses

Cause:
Existing filing State information was found for the data source and Input and cannot be added twice.

Action:
Clear out all filings for the Input and allow the server to remove the extra state information.

TCM-70025
There is no valid document id to run the command on.

Category:
Requests/Responses

Cause:
The command could not be executed because the last document failed to index and no document id was specified.

Action:
Either fix the indexing error for the last document in the file or specify a document id to apply the command to.

TCM-70026
The supporting content key value was not found in the command.

Category:
Requests/Responses

Cause:
No key value was specified for the supporting content command.

Action:
Add a supporting content key to the supporting content command.

TCM-70027
The supporting content file path was not found in the command.

Category:
Requests/Responses

Cause:
The supporting content file name was not found.

Action:
Add the supporting content's full path to the command.

TCM-70028
The annotation file path was not found in the command.

Category:
Requests/Responses

Cause:
The annotation file name was not found.

Action:
Add the annotation file's full path to the command.

TCM-70029
The file cleanup expire days {0} is invalid. The number of days must be greater than or equal to 0 and less than or equal to 30.

Category:
Requests/Responses

Cause:
An invalid file cleanup expire day count was provided.

Action:
Provide an integer value in the range from 0 to 30 days.

TCM-70030
The tenant {0} is not valid

Category:
Requests/Responses

Cause:
An invalid tenant name was given.

Action:
Call the MBean with a valid tenant name that is not empty.

TCM-70031
The specified directory {0} is not a valid input directory.

Category:
Requests/Responses

Cause:
An invalid input directory was provided.

Action:
Provide a directory that is in the input directories list.

TCM-70032
The specified directory {0} is not one of the current Input Directories.

Category:
Requests/Responses

Cause:
The input directory that was provided is not in the current set of Input Directories.

Action:
Specify an Input Directory that is currently in the Input Directory set.

TCM-70033
The Input Directory {0} already has tenant {1} associated with it. Only one tenant can be associated with a directory at one time

Category:
Requests/Responses

Cause:
The input directory that was provided is already associated with a tenant.

Action:
Either delete the existing tenant first or associate the tenant with a different directory.

TCM-70034
Tenant {0} is currently assigned to input directory {1}. A tenant can only be associated with one directory.

Category:
Requests/Responses

Cause:
The tenant name provided is already associated with an input directory.

Action:
Either delete the existing tenant association or provide a unique tenant for the directory.

TCM-71002
The input source cannot set up the stage path correctly.

Category:
Requests/Responses

Cause:
The plugin encountered an error trying to set up the stage path.

Action:
Check to make sure the plugin can get to the machine name.

TCM-71003
Encountered error {0} while writing to the error file {1}

Category:
Requests/Responses

Cause:
An error occurred while writing to the error file.

Action:
Check the disk, path, and user permissions.

TCM-71004
The failed path {0} cannot be initialized for processing.

Category:
Requests/Responses

Cause:
The failed directory could not be initialized.

Action:
Check the permissions to the Input Directory and subdirectories.

TCM-71005
The file mask {0} is invalid because it contains path information in addition to the file mask. Remove the additional path information.

Category:
Requests/Responses

Cause:
The file mask has at least a partial path in it, which is not supported.

Action:
Remove the path portion of the file mask

TCM-71006
Cannot lock the input file {0} for processing.

Category:
Requests/Responses

Cause:
The input file could not be locked for processing.

Action:
Make sure another program isn't accessing the file.

TCM-71007
Cannot save file {0} since a file with the same name already exists there

Category:
Requests/Responses

Cause:
The user tried to upload a sample file with a name that already exists in the directory

Action:
Specify a unique name before uploading to the sample directory

TCM-71008
Cannot save the given file to the sample directory. Error message provided is: {0}.

Category:
Requests/Responses

Cause:
The sample file could not be saved to the sample directory.

Action:
Check the embedded exception for more details.

TCM-71009
The state file {0} cannot be created.

Category:
Requests/Responses

Cause:
The state file could not be created.

Action:
Check the stage directory to make sure that it has enough space and the correct permissions.

TCM-71010
The state file {0} cannot be updated.

Category:
Requests/Responses

Cause:
The state file could not be updated.

Action:
Check the stage directory to make sure that it has enough space and the correct permissions.

TCM-71011
No instances of the delimiter {0} were found in the current line of the input file

Category:
Requests/Responses

Cause:
The delimiter is missing for the input file line

Action:
Check the delimiter in the Input Definition and make sure it's the correct one for the input file

TCM-71012
The file {0} is 0 bytes in length and cannot be processed.

Category:
Requests/Responses

Cause:
An attempt was made to process an input file that has 0 bytes.

Action:
Process a file with data in it.

TCM-71013
The file state information cannot be loaded for data source {0}

Category:
Requests/Responses

Cause:
Error loading the filing state for the input file

Action:
Examine the database and any inner exceptions to determine the cause of the load error

TCM-71014
The filing state information cannot be found for data source {0}.

Category:
Requests/Responses

Cause:
The filing state could not be found for the input file

Action:
Check the database to make sure that the filing state entry still exists

TCM-90001
Conversation ID not found: {0}

Category:
Session

Cause:
Conversation identifier was not found in current session.

Action:
Start over, if the problem persists, contact your system administrator.

TCM-90002
Task Context is unavailable.

Category:
Session

Cause:
Workflow Task Context was not available.

Action:
Start over. If the problem persists, contact your system administrator.

TCM-90003
Invalid Task ID: {0}

Category:
Session

Cause:
Task ID provided was not available in request or in cache.

Action:
Start over, if the problem persists, contact your system administrator.

TCM-90004
Task {0} already acquired by {1}

Category:
Session

Cause:
The chosen workflow task has already been acquired by another user.

Action:
Select another task and try again.

TCM-90005
Username cannot be changed.

Category:
Session

Cause:
Username cannot be changed without changing sessions.

Action:
Logout and log in with the desired user.

TCM-90006
Username cannot be null.

Category:
Session

Cause:
Username passthrough is set to TRUE. Username is required with this setting.

Action:
Provide a valid username and try again.

TCM-91000
An unexpected system error occurred. Contact your system administrator for support.

Category:
Programmatic

Cause:
An error has occurred.

Action:
Contact Oracle Support Services for help determining the cause.

TCM-91001
SolutionParameter not found for: SolutionNamespace={0}, CommandNamespace={1}, ConfigurationNamespace={2}, ParameterKey={3}

Category:
Configuration

Cause:
SolutionParameter was not found in "AXF_SOLUTION_PARAMETERS" table for the provided SolutionNamespace, CommandNamespace, ConfigurationNamespace, ParameterKey.

Action:
Verify that the "AXF_SOLUTION_PARAMETERS" table contains this value.

TCM-91002
SystemParameter not found for: Namespace={0}, ParameterType={1}, ParameterKey={2}

Category:
Configuration

Cause:
SystemParameter was not found in "AXF_SYSTEM_PARAMETERS" table for the provided SolutionNamespace, ParameterType, ParameterKey.

Action:
Verify that the "AXF_SYSTEM_PARAMETERS" table contains this value.

TCM-91003
There was an error with the supplied XPath: {0}

Category:
Configuration

Cause:
There was an error with the provided XPath

Action:
Verify XPATH configuration in "AXF_XPATH_ATTRIBUTE" table

TCM-91004
SolutionNamespace cannot be modified in an existing Conversation

Category:
Programmatic

Cause:
SolutionNamespace cannot be modified in an existing Conversation identifier.

Action:
Start a new Conversation identifier for the new SolutionNamespace.

TCM-91005
SolutionNamespace not configured: {0}

Category:
Configuration

Cause:
Provided SolutionNamespace was not configured in the "AXF_SOLUTIONS" table.

Action:
Ensure the SolutionNamespace entered has a matching entry in the "AXF_SOLUTIONS" table.

TCM-91006
System cache failure

Category:
Process

Cause:
The system cache failed.

Action:
Contact Oracle Support Services with all log information, and restart your server.

TCM-91007
Unable to load command {0} using configured command class {1}

Category:
Configuration

Cause:
Failed to create the instance of command provided in the "AXF_COMMANDS" table

Action:
Check configuration entry in "AXF_COMMANDS" table and verify that the matching class has been loaded in the application server

TCM-91008
Unable to find command "{0}" in the database.

Category:
Configuration

Cause:
Unable to find the provided command in "AXF_COMMANDS" table

Action:
Check the command entry in "AXF_COMMANDS" table

TCM-91009
Unable to create named connection: {0}

Category:
Configuration

Cause:
Failed to find the workflow connection information from the Imaging system

Action:
Check configuration entry in "AXF_SOLUTION_ATTRIBUTE" table and the corrresponding entry in "CONNECTION_DETAILS" table.

TCM-91010
Unable to create named connection without a provider specified

Category:
Configuration

Cause:
Failed to create named connection without a provider specified

Action:
Check configuration entry in "AXF_SOLUTION_ATTRIBUTE" table and the corrresponding entry in "CONNECTION_DETAILS" table.

TCM-91014
Solution Parameter Key {0} has an invalid value of {1} for Solution Namespace = {2} -- Command Namespace = {3} -- Configuration Namespace = {4}

Category:
Configuration

Cause:
The Solution Parameter Key has an invalid value in "AXF_SOLUTION_PARAMETERS" for the provided SolutionNamespace, ParameterType, ParameterKey.

Action:
Verify the configuration parameter in "AXF_SYSTEM_PARAMETERS" table for the Redirect Command.

TCM-91015
Error executing pl/sql procedure: {0} using connection: {1} for conversation: {2}

Category:
Configuration

Cause:
Failed to execute pl/sql procedure in UpdateTaskFromProcedureCommand.

Action:
Verify the configuration parameter in "AXF_SYSTEM_PARAMETERS" table for UpdateTaskFromProcedureCommand.

TCM-91016
Unable to retrieve database connection using JNDI name: {0}

Category:
Configuration

Cause:
Failed to retrieve the JNDI name from Application Server.

Action:
Verify the configuration parameter in "AXF_SYSTEM_PARAMETERS" table and ensure that JNDI is setup correctly in application server.

TCM-91017
Unable to retrieve the web root context from the application server.

Category:
Configuration

Cause:
Failed to retrieve the web root context from the application server.

Action:
Contact Oracle Support Services for help determining cause.

TCM-91018
SolutionNamespace attribute not found for: Namespace={0}, ParameterKey={1}

Category:
Configuration

Cause:
SolutionNamespace attribute was not found in the "AXF_SOLUTION_ATTRIBUTES" table for the BPEL_CONNECTION key.

Action:
Check the "AXF_SOLUTION_ATTRIBUTES" Table for the missing configuration.

TCM-91019
Command Parameter Key {0} has an invalid value of {1} for Solution Namespace = {2}, Command Namespace = {3}

Category:
Configuration

Cause:
Command Parameter Key is missing, invalid or empty for Solution Namespace.

Action:
Check the request parameters for command.

TCM-91020
Unable to decode the value in URL {0}

Category:
Configuration

Cause:
This encoding is not supported.

Action:
Check the encoding URL value.

TCM-91021
UCM unable to process the request - {0}

Category:
Configuration

Cause:
UCM is unable to process the request.

Action:
Check the UCM configuration.

TCM-91022
Please login as Admin user to perform the grant operation.

Category:
Session

Cause:
You are trying to perform the operation as a normal user. Only admin user can perform this operation.

Action:
Login as Admin user to perform this operation.

TCM-91023
Error accessing credential from CSF having key {0}

Category:
Configuration

Cause:
An error occurred while accessing a credential key in the credential store.

Action:
Ensure that the correct key was provided and the credentials are properly configured in the credential store.

TCM-91201
Unable to create sorts for workflow

Category:
Configuration

Cause:
Got the workflow exception while creating ordering

Action:
Check permission for workflow user and workflow log

TCM-91202
Unable to create predicates for workflow

Category:
Configuration

Cause:
Got the workflow exception while creating predicate

Action:
Check permission for workflow user and workflow log

TCM-91203
Payload column is not supported for filtering

Category:
Configuration

Cause:
Payload column is not supported for filtering

Action:
Remove payload from column filtering

TCM-91204
Attributes list is null or empty

Category:
Configuration

Cause:
Attributes list was null or empty

Action:
Supply at least one attribute

TCM-91205
Unable to find the value specified by xpath : {0}

Category:
Configuration

Cause:
Xpath found no matching element in the workload payload.

Action:
Verify the xpath value in "AXF_XPATH_ATTRIBUTES" table and that the workflow payload has a corresponding entry.

TCM-91206
Workflow admin userid is missing

Category:
Configuration

Cause:
Failed to get the workflow admin userid.

Action:
Check the workflow admin userid in CSF of application server for the matching alias key in "CONNECTION_DETAILS" table.

TCM-91207
Workflow admin password is missing

Category:
Configuration

Cause:
Failed to get the workflow admin password.

Action:
Check the workflow admin password in CSF of application server for the matching alias key in "CONNECTION_DETAILS" table.

TCM-91208
Workflow provider url is missing

Category:
Configuration

Cause:
Failed to get the workflow provider url.

Action:
Check the host and port in "CONNECTION_DETAILS" database table

TCM-91209
Unable to authenticate from workflow

Category:
Configuration

Cause:
Failed to authenticate with workflow server.

Action:
Check the workflow password in CSF of application server for the matching alias key in "CONNECTION_DETAILS" table.

TCM-91210
Unable to locate the security member specified

Category:
Configuration

Cause:
Failed to locate the security policy store.

Action:
Check the application server security configuration for authentication.

TCM-91211
Unable to locate the security store identity

Category:
Configuration

Cause:
Failed to locate the security store identity.

Action:
Check the application server security configuration for authentication.

TCM-91212
User {0} does not exist in the policy store.

Category:
Configuration

Cause:
User did not exist in the policy store.

Action:
Validate the user in the policy store.

TCM-91213
Unable to find the users in the policy store.

Category:
Configuration

Cause:
Failed to find the users in the policy store.

Action:
Verify that users exist in the policy store.

TCM-91214
Unable to find the roles in the policy store.

Category:
Configuration

Cause:
Failed to find the roles in the policy store

Action:
Check the application server security configuration for authentication

TCM-91215
Unable to find the policies in the policy store

Category:
Configuration

Cause:
Unable to find the policies in the policy store

Action:
Check the application server security configuration for authentication

TCM-91216
Unable to get the payload value for {0}

Category:
Configuration

Cause:
Failed to find an element in workflow payload using xpath

Action:
Verify the xpath value in "AXF_XPATH_ATTRIBUTES" table and the workflow payload has it

TCM-91217
Unable to load XML file '{0}' into XML Document

Category:
Configuration

Cause:
Failed to load XML file into XML Document to create the views.

Action:
Check the XML file permissions, format, and location on disk.

TCM-91218
View name is blank. It must be set to create a view. XML = {0}

Category:
Configuration

Cause:
View name was blank in the provided XML file.

Action:
Ensure that the view name is not empty in the XML file and node tag is /workflowSet/FFMSet/FFMDefinition/[<view name>]/FFMDetail/name.

TCM-91219
User name is blank. It must be set to create a view. XML = {0}

Category:
Configuration

Cause:
User name was blank, it must be set to create a view.

Action:
Ensure that the user name is not blank in the XML file and node tag is /workflowSet/viewSet/viewDefinition/[<view name>]//userList/user[<user>].

TCM-91220
User name or realm is blank. It must be set to create a view. XML = {0}

Category:
Configuration

Cause:
User name or realm was blank.

Action:
Ensure that the user name or realm is blank in the XML file.

TCM-91221
View Filter Column name is blank. It must be set to create a view. XML = {0}

Category:
Configuration

Cause:
View filter Column name was blank.

Action:
Ensure that the View Filter Column name is not blank in the XML file and node tag is /workflowSet/viewSet/viewDefinition/[<view name>]//userViewDetail/viewPredicate/clause[<position>]/column.

TCM-91222
Filter Operation is blank. It must be set to create a view. XML = {0}

Category:
Configuration

Cause:
Filter operation was blank.

Action:
Ensure that the Filter Operation is not blank in the XML file and node tag is /workflowSet/viewSet/viewDefinition/[<view name>]//userViewDetail/viewPredicate/clause[<position>]/operator.

TCM-91223
Filter Value is blank. XML = {0}

Category:
Configuration

Cause:
Filter value was blank.

Action:
Ensure that the Filter Value is not blank in the XML file and node tag is /workflowSet/viewSet/viewDefinition/[<view name>]//userViewDetail/viewPredicate/clause[<position>]/value.

TCM-91224
View Ordering column name is blank. XML = {0}

Category:
Configuration

Cause:
View ordering column name was blank.

Action:
Ensure that the View ordering column name is not blank in the XML file and node tag is /workflowSet/viewSet/viewDefinition/[<view name>]/userViewDetail/viewOrdering/clause[<position>]/column.

TCM-91225
View Ordering sort order is blank. XML = {0}

Category:
Configuration

Cause:
View ordering sort order was blank.

Action:
Ensure that the View ordering sort order is not blank in the XML file and node tag is /workflowSet/viewSet/viewDefinition/[<view name>]/userViewDetail/viewOrdering/clause[<position>]/sortOrder

TCM-91226
View Creation failed. XML = {0}

Category:
Configuration

Cause:
Failed to create the workflow View

Action:
Check user permissions to create the view and also check the workflow server log

TCM-91227
View Column name was blank. XML = {0}

Category:
Configuration

Cause:
View column name was blank, it must be set to create a view

Action:
View Column name is blank in the XML fileand node tag is /workflowSet/viewSet/viewDefinition/[<view name>]/userViewDetail/viewColumns/column[<position>]

TCM-91228
Unable to get the next task

Category:
Configuration

Cause:
Failed to retrieve the next task from workflow.

Action:
There may be no tasks for this user in workflow. Check the workflow server log.

TCM-91229
Unable to get list of tasks

Category:
Configuration

Cause:
Failed to get list of tasks

Action:
Workflow server may be not running or password is not correct in CSF. Check the workflow server log

TCM-91230
Unable to get list of views

Category:
Configuration

Cause:
Failed to get list of views

Action:
Workflow server may be not running or password is not correct in CSF. Check the workflow server log

TCM-91231
Unable to acquire task id {0} for user {1}

Category:
Configuration

Cause:
Failed to acquire task id from workflow.

Action:
The task may be already acquired by another user. Check the workflow server log.

TCM-91232
got the stale object from workflow

Category:
Configuration

Cause:
The task from workflow is out of date.

Action:
Log out from the application and try again.

TCM-91233
Unable to release task id {0} for user {1}

Category:
Configuration

Cause:
Failed to release task id from workflow.

Action:
Verify that the task can be acquired by the current user. Check the workflow server log.

TCM-91234
Unable to get the task detail for {0}

Category:
Configuration

Cause:
Failed to get the task detail from workflow.

Action:
Verify that the task is not already completed or purged in workflow.

TCM-91235
Task ID is null

Category:
Configuration

Cause:
Task Id was invalid or null.

Action:
Logout from application and try again.

TCM-91236
Unable to update the task for {0}

Category:
Configuration

Cause:
Failed to update the task in workflow.

Action:
Verify that the task may be acquired to update the payload. Check the workflow server log.

TCM-91237
Unable to update outcome for {0}

Category:
Configuration

Cause:
Failed to update the outcome in workflow.

Action:
Verify that the task may be acquired to update and that the outcome is valid. Check the workflow server log.

TCM-91238
Unable to acquire next available task for {0}

Category:
Configuration

Cause:
Failed to acquire next available task in workflow.

Action:
There may be no task for this user in the workflow. Check the workflow server log.

TCM-91239
Unable to update transaction ID in workflow payload

Category:
Configuration

Cause:
Failed to update transaction ID in workflow payload.

Action:
Verify Transaction field exists in the workflow payload.

TCM-91240
Unable to get comments

Category:
Configuration

Cause:
Failed to get comments from workflow.

Action:
Check the user's permission to get comments. Check the workflow server log.

TCM-91241
Comment is null.

Category:
Configuration

Cause:
The value of Comment was null.

Action:
Contact your system administrator.

TCM-91242
Unable to update comment in workflow

Category:
Configuration

Cause:
Failed to update the comment in workflow.

Action:
User may not have permission to update the comment. Check the workflow server log.

TCM-91243
Invalid URL for identity search URL

Category:
Configuration

Cause:
Received URL was Invalid for identity search

Action:
Check the URL for identity search in the database

TCM-91244
Unable to open the connection for identity search URL

Category:
Configuration

Cause:
Failed to open the connection for identity search URL.

Action:
Verify that the Web service is available for identity search.

TCM-91245
Unable to parse the XML date received from identity search URL

Category:
Configuration

Cause:
Failed to parse XML date received from identity search URL

Action:
Check the XML format of input file as it may be invalid. There may be some invalid tag in the file

TCM-91246
Unable to acquire the task. Task is not assigned to the group or is assigned to a different user.

Category:
Configuration

Cause:
Either the task was not assigned to the group or it was assigned to a different user.

Action:
Select another task from the list.

TCM-91247
Invalid Task attribute Key {0}

Category:
Configuration

Cause:
Received Invalid Task attribute Key.

Action:
Check your configuration or command for the attribute Key value

TCM-92002
Access is denied.

Category:
Requests/Responses

Cause:
User does not have access to the requested information.

Action:
Ensure user is defined with proper permissions.

TCM-92501
Duplicate annotation IDs exist

Category:
Requests/Responses

Cause:
Duplicate annotation IDs exist.

Action:
Ensure that each annotation has a unique id. Annotations cannot be added more than once.

TCM-92502
Null or empty annotation Id specified

Category:
Requests/Responses

Cause:
Null or empty annotation Id specified.

Action:
Ensure that annotation id is not null or empty.

TCM-92503
Null annotation object specified

Category:
Requests/Responses

Cause:
Invalid annotation object specified.

Action:
Ensure that annotation object is not null and has a valid Id.

TCM-92504
Annotation list is Null

Category:
Requests/Responses

Cause:
Annotation list to search is null.

Action:
Ensure that annotation list object is not Null.

TCM-92505
Annotation requires at least three points

Category:
Requests/Responses

Cause:
This annotation requires at least three points.

Action:
Provide three points, or use a LineAnnot object.

TCM-92506
There was an error deserializing an annotation file for this document.

Category:
Requests/Responses

Cause:
There was an error deserializing an annotation file for this document.

Action:
Check the nested exception details for diagnostic information.

TCM-92507
There was an error serializing an annotation file for this document.

Category:
Requests/Responses

Cause:
There was an error serializing an annotation file for this document.

Action:
Check the nested exception details for diagnostic information.

TCM-92508
An annotation list cannot be merged with itself

Category:
Requests/Responses

Cause:
An annotation list cannot be merged with itself.

Action:
Specify a unique list of annotations.

TCM-92509
A null value was supplied where an AnnotPoint object is expected.

Category:
Requests/Responses

Cause:
A null value was supplied where an AnnotPoint object is expected

Action:
Provide a valid AnnotPoint object

TCM-92510
The requested scale is not within the allowed value range; {0}-{1}

Category:
Requests/Responses

Cause:
The requested scale is not within the allowed value range.

Action:
Provide a proper scale value within the supported range.

TCM-92511
Page number must be a positive value.

Category:
Requests/Responses

Cause:
Page number must be a positive value.

Action:
Provide a page number that is greater than zero.

TCM-92512
Bounding rectangle specified is empty.

Category:
Requests/Responses

Cause:
Bounding rectangle specified is empty.

Action:
Supply a non-null, non-empty rectangle definition.

TCM-92513
The Document Store provider {0} cannot be loaded

Category:
Requests/Responses

Cause:
The specified Document Store could not be loaded

Action:
Make sure the provided class is correct and that it exists in the classpath

TCM-92514
Redact annotation cannot be assigned HIDDEN security.

Category:
Requests/Responses

Cause:
Redact annotation cannot be assigned HIDDEN security.

Action:
Use a different security setting.

TCM-92515
The page annotations include at least one annotation from another page.

Category:
Requests/Responses

Cause:
An attempt was made to replace page annotations with at least one annotation from a different page.

Action:
Supply only annotations for the page specified.

TCM-92516
Error deserializing annotations. InputStream is null.

Category:
Requests/Responses

Cause:
Error deserializing annotations. InputStream is null.

Action:
Supply a serialized annotation stream.

TCM-92517
Transformation process returned error code {0}.

Category:
Requests/Responses

Cause:
Transformation process returned an error code.

Action:
See the transformation process return code for diagnostic information.

TCM-92518
There was an error launching the external transformation process: {0} {1}

Category:
Requests/Responses

Cause:
There was an error launching the external transformation process

Action:
The transformation process failed unexpectedly. Check nested exception details for diagnostic information.

TCM-92521
The path specified for GdFontPath configuration is invalid.

Category:
Requests/Responses

Cause:
The path specified for GdFontPath configuration is invalid.

Action:
Provide a valid path to a directory containing True Type Fonts.

TCM-92522
There was an error reading TIFF headers. The file may be corrupt.

Category:
Requests/Responses

Cause:
There was an error reading TIFF headers. The file may be corrupt.

Action:
Check permissions and free space in the server temp directory.

TCM-92523
There was an error authenticating the user. Please login and retry.

Category:
Requests/Responses

Cause:
There was an error authenticating the user.

Action:
Check the nested exception details for diagnostic information.

TCM-92524
There was an error getting the document annotations. Please verify the document ID.

Category:
Requests/Responses

Cause:
There was an error getting the document annotations. Please verify the document ID.

Action:
Check the nested exception details for diagnostic information.

TCM-92525
There was an error getting the document. Please verify the document ID.

Category:
Requests/Responses

Cause:
There was an error getting the document. Please verify the document ID.

Action:
Check the nested exception details for diagnostic information.

TCM-92700
The cache config file can not be found

Category:
Requests/Responses

Cause:
The cache configuration file was not found.

Action:
Inspect the Cache jar and verify that the CacheConfig.xml file exists.

TCM-92701
The cache storage configuration is not in the config file

Category:
Requests/Responses

Cause:
The configuration for the cache storage adaptor could not be found.

Action:
Add a valid storage adaptor to the cache config file.

TCM-92702
The cache configuration file cannot be read for processing

Category:
Requests/Responses

Cause:
The cache configuration file could not be read.

Action:
Please examine the inner exception to determine why the read operation failed.

TCM-92703
The cache storage adaptor could not be found

Category:
Requests/Responses

Cause:
The storage adaptor implementation could not be found.

Action:
Check the cache config file and verify that the storage adaptor is correct.

TCM-92704
The cache storage adaptor could not be instantiated

Category:
Requests/Responses

Cause:
The storage adaptor could not be loaded.

Action:
Examine the adaptor code and verify it has a parameterless constructor.

TCM-92705
Error writing to Lock file {0}.

Category:
Requests/Responses

Cause:
There was a problem writing to a file.

Action:
Check the inner exception to determine the cause of the error.

TCM-92706
A lock could not be acquired on lock file {0}.

Category:
Requests/Responses

Cause:
The lock file could not be locked and validated.

Action:
Check the inner exception to determine the cause of the error.

TCM-92707
The directory {0} could not be created.

Category:
Requests/Responses

Cause:
The specified directory could not be created.

Action:
Examine the path to make sure it is not full and that the server account has write privileges to it.

TCM-92708
The Document ID {0} is not valid.

Category:
Requests/Responses

Cause:
The Document ID that was specified is not valid.

Action:
Pass in a valid Document ID to the cache service.

TCM-92709
An error occurred while queuing the cache request for processing.

Category:
Requests/Responses

Cause:
An exception was raised while attempting to queue the cache request.

Action:
Look at the inner exception to get details on the cause of the error.

TCM-92710
The cache repository interface configuration value was not found.

Category:
Requests/Responses

Cause:
The configuration for the repository interface could not be found.

Action:
Add a valid repository interface to the cache config file.

TCM-92711
The configuration string for the repository interface could not be parsed.

Category:
Requests/Responses

Cause:
The configuration information for the repository interface is not valid.

Action:
Look at the repository configuration and make sure that the values are separated by semicolons.

TCM-92712
The viewer cache imaging repository interface could not be initialized.

Category:
Requests/Responses

Cause:
The viewer cache imaging repository interface could not be initialized for processing.

Action:
Examine the inner exception to get specifics on why the initialization failed.

TCM-92713
The viewer cache repository could not retrieve requested document {0}.

Category:
Requests/Responses

Cause:
The requested document could not be retrieved from the viewer cache repository.

Action:
Examine the inner exception to get specifics on why the operation failed.

TCM-92714
The viewer cache repository interface {0} could not be found.

Category:
Requests/Responses

Cause:
The cache repository implementation could not be found.

Action:
Check the cache config file and verify that the repository configuration is correct.

TCM-92715
An instance of the viewer cache repository {0} could not be created.

Category:
Requests/Responses

Cause:
The cache repository could not be loaded.

Action:
Examine the inner exception and repository implementation to determine the load error.

TCM-92716
The viewer cache repository could not get the annotations for document {0}.

Category:
Requests/Responses

Cause:
The requested annotation set could not be retrieved from the viewer cache repository.

Action:
Examine the inner exception to get specifics on why the operation failed.

TCM-92717
The file {0} can not be found for processing.

Category:
Requests/Responses

Cause:
The requested file could not be found for processing.

Action:
Determine if the file exists and has the correct permissions.

TCM-92718
{0} is not a valid document page.

Category:
Requests/Responses

Cause:
The requested page to retrieve from cache is invalid.

Action:
Check the cache request and verify the requested page is greater than 0.

TCM-92719
The requested page range of {0} to {1} is not valid.

Category:
Requests/Responses

Cause:
The requested cache page range is invalid.

Action:
Check the end page of the cache request and verify that it is greater than the start page.

TCM-92720
The cache directory for object {0} could not be locked for processing

Category:
Requests/Responses

Cause:
The cache lock file failed verification.

Action:
Check to make sure that the imaging services have full access to the directory and it is not shared with other imaging systems.

TCM-92721
A failure occurred while attempting to get configuration values from imaging.

Category:
Requests/Responses

Cause:
An error was encountered while trying to look up the configuration data.

Action:
Look at the nested error to get the exact cause of the error.

TCM-92722
Page number {0} is invalid, document {1} only has {2} pages.

Category:
Requests/Responses

Cause:
The requested page is not in the document.

Action:
Request a page number that is in the document's page range.

TCM-92723
Processing was aborted while waiting for results.

Category:
Requests/Responses

Cause:
The operation was stopped while waiting for the operations results.

Action:
Check the logs to see if an operation was forcibly stopped.

TCM-92724
An error was encountered while trying to read or write to the image stream.

Category:
Requests/Responses

Cause:
A failure occurred while reading or writing from an image.

Action:
Check the inner exception to determine the cause of the error.

TCM-92725
The image could not be converted to a PNG stream because the image writer could not be found or have its options set.

Category:
Requests/Responses

Cause:
The PNG image writer could not be loaded or could not have its options set.

Action:
Check the Java installation and verify all the libraries are installed.

TCM-92726
Could not get the annotation security for document {0}.

Category:
Requests/Responses

Cause:
The document's annotation security could not be determined.

Action:
Check the inner exception to determine the cause of the error.

TCM-92727
This document contains annotations that prevent the user from accessing this document in its raw format

Category:
Requests/Responses

Cause:
This document contains annotations that prevent the user from accessing this document in its raw format.

Action:
Export to TIFF with the annotations burned in or contact your administrator for access to the native format.

TCM-92728
The image information for document {0}, page {1} could not be read.

Category:
Requests/Responses

Cause:
The image information could not be read.

Action:
Check the inner exception to determine the cause of the error.

TCM-92729
Error loading the document properties for document {0}

Category:
Requests/Responses

Cause:
Failed to get the document properties.

Action:
Check the inner exception to determine the cause of the error.

TCM-92730
The rendering cache is disabled and not accepting requests.

Category:
Requests/Responses

Cause:
The rendering cache feature is disabled.

Action:
Set the ViewerCacheDays and ViewerCachePath configuration values in the configuration MBean to enable caching.

TCM-92731
Document {0} failed image conversion and cannot be stored in the cache at this time. Please review the server log for details on the cause of the error.

Category:
Requests/Responses

Cause:
The requested document could not be converted to the appropriate image format.

Action:
Examine the log files to determine the cause of the conversion errors.

TCM-92732
The credential for storing the encryption key was not found.

Category:
Requests/Responses

Cause:
The credential for storing the encryption key was not found.

Action:
Verify the credential for the encryption key is available.

TCM-92733
A failure occurred while encrypting the document.

Category:
Requests/Responses

Cause:
A failure occurred while encrypting the document.

Action:
Check the inner exception to determine the cause of the error.

TCM-92734
A failure occurred while generating the encryption key.

Category:
Requests/Responses

Cause:
A failure occurred while generating the encryption key.

Action:
Check the inner exception to determine the cause of the error.

TCM-92735
A failure occurred while retrieving the encryption key.

Category:
Requests/Responses

Cause:
A failure occurred while retrieving the encryption key.

Action:
Check the inner exception to determine the cause of the error.

TCM-92736
A failure occurred while storing the encryption key.

Category:
Requests/Responses

Cause:
A failure occurred while storing the encryption key.

Action:
Check the inner exception to determine the cause of the error.

TCM-92737
A failure occurred while generating the encryption cipher.

Category:
Requests/Responses

Cause:
A failure occurred while generating the encryption cipher.

Action:
Check the inner exception to determine the cause of the error.

TCM-92738
A failure occurred while using the cipher for encryption.

Category:
Requests/Responses

Cause:
A failure occurred while using the cipher for encryption.

Action:
Check the inner exception to determine the cause of the error.

TCM-92739
A failure occurred while using the cipher for decryption.

Category:
Requests/Responses

Cause:
A failure occurred while using the cipher for decryption.

Action:
Check the inner exception to determine the cause of the error.

TCM-92740
No priority value was specified for the add to cache request.

Category:
Requests/Responses

Cause:
A priority was not specified for the add request.

Action:
Call the add request with a priority value.

TCM-92741
An error occurred while queuing the cache request. The Oracle WebCenter Content: Imaging Viewer Cache application (imaging-vc) was not found.

Category:
Requests/Responses

Cause:
The viewer cache application deployment was not found.

Action:
Check the domain configuration an verify that the viewer cache application is properly deployed.

TCM-92742
This document content is sealed. IRM content cannot be rendered.

Category:
Requests/Responses

Cause:
This document content is sealed. IRM content cannot be rendered.

Action:
Download the native document and use Oracle IRM Desktop to access this file content.

TCM-92999
An error occurred in a subsystem. {0}

Category:
Requests/Responses

Cause:
An error occurred in a rendering subsystem.

Action:
Review the logs for the error. You may need to contact Oracle Support Services to resolve the issue.

TCM-99001
The repository definition identifier, {0}, is not valid.

Category:
Requests/Responses

Cause:
An attempt was made to add a repository configuration with a duplicate identifier.

Action:
Use a unique identifier.

TCM-99002
The repository definition name, {0}, is not valid.

Category:
Requests/Responses

Cause:
An attempt was made to add a repository configuration with a duplicate name.

Action:
Use a unique name.

TCM-99003
The repository definition identifier, {0}, is not unique.

Category:
Requests/Responses

Cause:
An attempt was made to add a repository configuration with a duplicate identifier.

Action:
Use a unique identifier.

TCM-99004
The repository definition name, {0}, is not unique.

Category:
Requests/Responses

Cause:
An attempt was made to add a repository configuration with a duplicate name.

Action:
Use a unique name.

TCM-99005
A system repository definition already exists.

Category:
Requests/Responses

Cause:
An attempt was made to add a system repository configuration when one already exists.

Action:
Remove the existing system repository first.

TCM-99006
The destination repository is read only and does not support this operation.

Category:
Requests/Responses

Cause:
An attempt was made to copy or move a document to a repository that is not writeable.

Action:
Change the destination repository to one that is writeable.

TCM-99007
The destination repository is not the same as the source repository.

Category:
Requests/Responses

Cause:
An attempt was made to move a document to a different repository.

Action:
Ensure that the source and destination repositories are the same.

TCM-99008
The destination repository is not the same type as the source repository.

Category:
Requests/Responses

Cause:
An attempt was made to move a document to a different type of repository.

Action:
Ensure that the source and destination repositories are the same type.

TCM-99009
The repository must be initialized to support WebCenter Content: Imaging prior to creating a connection.

Category:
Requests/Responses

Cause:
An attempt was made to create a connection to a system that is not yet configured.

Action:
Ensure that target UCM system is configured prior to creating a connection.

32

UCM-CS-000001 to UCM-CS-800280

UCM-CS-000001
general exception

Category:
Logging

Cause:
An exception occurred in the content server.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-000002
Error:

Category:
Logging

Cause:
An error occurred in the content server.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-000003
Unknown system error encountered.

Category:
Logging

Cause:
An error occurred in the content server.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-000004
Unknown error encountered.

Category:
Logging

Cause:
The system encountered an unknown error.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-000005
Null pointer is dereferenced.

Category:
Logging

Cause:
A null pointer exception occurred in the content server.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-000006
Trace Message:({0})

Category:
Logging

Cause:
A general trace message from the content server.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-000007
Out of memory exception

Category:
Logging

Cause:
An out of memory exception occurred in the content server.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-000008
service exception

Category:
Logging

Cause:
A service exception occurred in the content server.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-000009
data exception

Category:
Logging

Cause:
A data exception occurred in the content server.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001001
The NativeOsUtils class is not loaded.

Category:
Configuration

Cause:
The required library 'NativeOsUtils' was not successfully loaded.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001002
Native file operations are disabled.

Category:
Configuration

Cause:
The system's ability to do native file operations has been disabled.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001003
The platform {0} is not supported.

Category:
Configuration

Cause:
The specified operating system does not supported.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001004
The platform {0} is not supported for this operation.

Category:
Configuration

Cause:
The specified operating system did not support the specified operation.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001005
The argument {0} is missing.

Category:
Configuration

Cause:
The method or service was missing the required argument.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001006
{0} is missing from {1}.

Category:
Configuration

Cause:
The method or service was missing the required argument.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001007
Unable to load database queries in table {0} for component {1}. The table does not exist.

Category:
Configuration

Cause:
An error was encountered while loading the queries for the named component.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001008
The feature {0} is not installed.

Category:
Configuration

Cause:
The required feature has not been installed.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001009
The feature {0} is at level {1}, but level {2} is required.

Category:
Configuration

Cause:
An error was encountered while validating features. The requested feature is not supported.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001010
Incompatibility with feature {0} at level {1} has been detected.

Category:
Configuration

Cause:
The specified feature was incompatible with a feature provided either by the system or another component.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001011
The feature {0} does not match feature {1}.

Category:
Configuration

Cause:
The feature did not match an already installed feature.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001012
The feature {0} is installed at level {1}, but is also provided at level {2}.

Category:
Configuration

Cause:
The feature already existed at a later version.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-001013
The instance name {0} is not valid.

Category:
Configuration

Cause:
The instance name specified contained illegal characters.

Action:
The instance name needs to be configured to be a valid name. Please check documentation for how to configure.

UCM-CS-001014
{0} component, version {1}, requires missing feature(s). {2}

Category:
Configuration

Cause:
For the specified component to function correctly it needs the listed features.

Action:
The components that provide the listed features need to be installed.

UCM-CS-005001
Unable to copy the file {0} to {1}.

Category:
Files

Cause:
An error occurred while copying files. An error occurred while copying files.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack. Details are usually given in the cause exception. Look for

messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005002
Unable to rename the file {0} to {1}.

Category:
Files

Cause:
An error occurred while renaming files. An error occurred while renaming files.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack. Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005003
Unable to open {0}.

Category:
Files

Cause:
An error occurred while opening the named file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005004
Unable to read {0}.

Category:
Files

Cause:
An error occurred while accessing a file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005005
Unable to write {0}.

Category:
Files

Cause:
An error occurred while writing a file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005006
The file is missing.

Category:
Files

Cause:
The specified file was missing.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005007
The file {0} does not exist.

Category:
Files

Cause:
The specified file did not exist.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005008
The file {0} already exists.

Category:
Files

Cause:
The file already existed in the system.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005009
The file {0} already exists in {1} directory.

Category:
Files

Cause:
The file already existed in the named directory.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005010
File I/O error encountered while reading from file.

Category:
Files

Cause:
An error occurred while reading the file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005011
File I/O error encountered while writing to file.

Category:
Files

Cause:
An error occurred while writing the specified file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005012
Unable to delete {0}.

Category:
Files

Cause:
An error occurred while deleting the specified file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005013
Could not create the file {0}.

Category:
Files

Cause:
An error occurred while creating the specified file. An error occurred while creating the specified file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack. Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005014
File I/O error encountered while saving to file {0}.

Category:
Files

Cause:
An error occurred while saving the specified file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005015
The file path {0} is invalid.

Category:
Files

Cause:
The specified file path was invalid.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005016
Unable to find the file {0}. This may be a problem with the virtual machine.

Category:
Files

Cause:
The system expected a file at the specified location, but it was missing.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005017
Unable to find the file {0}.

Category:
Files

Cause:
The system was unable to locate the file at the specified location.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005018
Error encountered while creating long-term lock {1} on directory {0}.

Category:
Files

Cause:
An error occurred while creating the long term lock.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005019
Unable to create the directory.

Category:
Files

Cause:
An error occurred while creating the directory.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005020
Unable to create directory {0}.

Category:
Files

Cause:
An error occurred while creating the specified directory.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005021
Directory {0} does not exist.

Category:
Files

Cause:
The system was unable to locate a directory at the specified location.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005022
File {0} does not exist.

Category:
Files

Cause:
The system was unable to locate a file at the specified location. The system was unable to locate a file at the specified location.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack. Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005023
Directory {0} cannot be accessed.

Category:
Files

Cause:
An error occurred while accessing the directory.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005024
File {0} cannot be accessed.

Category:
Files

Cause:
An error occurred while accessing the specified file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005025
Directory {0} is read-only.

Category:
Files

Cause:
A read-only directory was specified.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005026
File {0} is read-only.

Category:
Files

Cause:
A read-only file was specified.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005027
Directory {0} has an invalid path.

Category:
Files

Cause:
The system tried to access an invalid directory path.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005028
File {0} has an invalid path.

Category:
Files

Cause:
The system tried access an invalid file path.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005029
Accessing the directory {0} caused a system error.

Category:
Files

Cause:
An error was encountered while accessing the directory.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005030
File {0} caused a system error when accessed.

Category:
Files

Cause:
An error was encountered while accessing the file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005031
Unable to rename the file {0} to {1}.

Category:
Files

Cause:
An error was encountered when trying to rename the specified file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005032
The source file does not exist.

Category:
Files

Cause:
The specified file did not exist.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005033
The target file cannot be accessed.

Category:
Files

Cause:
The system was unable to access the specified file path.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005034
Unable to copy the file {0} to {1}. The source file does not exist.

Category:
Files

Cause:
An error was encountered while copying the file. The source file did not exist.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005035
Unable to copy the file {0} to {1}.

Category:
Files

Cause:
An error was encountered while copying the file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005037
File is locked by another process.

Category:
Files

Cause:
The file was locked by another process.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005038
File {0} cannot be deleted. It may be locked by another process.

Category:
Files

Cause:
An error was encountered while deleting the file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-005039
Long-term lock {0} cannot be created for agent {1}.

Category:
Files

Cause:
An error was encountered while attempting to create a long-term lock.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010001
Cannot end string with {0}.

Category:
Data

Cause:
During the parsing of a string, an illegal end character was encountered.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010002
Encountered an unterminated quote ({0}) at {1} in {2}.

Category:
Data

Cause:
During the parsing of a string, the parser found an unclosed quoted string.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010003
Error encountered converting data with {0} character encoding.

Category:
Data

Cause:
An encoding error was encountered while converting the data.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010004
Error encountered converting data with the default character encoding.

Category:
Data

Cause:
The system encountered an error while converting data with the default character encoding.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010005
An error occurred decoding the stream.

Category:
Data

Cause:
An error was encountered while decoding the data.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010006
Cannot find the parameter {0}.

Category:
Data

Cause:
The system could not find the named parameter.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010007
The table does not exist.

Category:
Data

Cause:
The named table did not exist or was not loaded into the resource container.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010008
The column {0} does not exist in this table.

Category:
Data

Cause:
The specified column did not exist in the table.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010009
Parameter {0} is not present.

Category:
Data

Cause:
The parameter was not defined in the current data set.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010010
Unable to parse result set {0}.

Category:
Data

Cause:
An error was encountered while parsing the result set.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010011
Unable to parse properties. Name-value pair {0} is missing an equal sign (=).

Category:
Data

Cause:
An error was encountered while parsing a property name-value pair.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010012
Error decoding the string. The string is badly formatted: {0}

Category:
Data

Cause:
An error was encountered while decoding the badly formatted string.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010013
A name-value pair is missing the name in GET or POST syntax.

Category:
Data

Cause:
An error was encountered while parsing the request.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010014
The input terminated before being able to read the line.

Category:
Data

Cause:
An error was encountered while reading the input stream.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010015
The stream terminated before being able to read HTTP protocol line.

Category:
Data

Cause:
An error was encountered while reading the input stream.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010016
Unable to parse data; the request method was not specified.

Category:
Data

Cause:
An error was encountered while parsing the input stream. The request method has not been specified.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010017
The POST request did not send sufficient data.

Category:
Data

Cause:
An error was encountered while parsing the request.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010018
Unable to read the stream to determine the format.

Category:
Data

Cause:
An error was encountered while processing the server request.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010019
Unable to read additional bytes.

Category:
Data

Cause:
An error was encountered while processing the server file request.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-010020
Client terminated the upload of file {0}.

Category:
Data

Cause:
The client terminated the upload of the file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050001
illegal state

Category:
Programmatic

Cause:
Something put the system into an unexpected error; this is a generic error.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050002
The transaction listener {0} failed to close.

Category:
Programmatic

Cause:
The transaction failed to close when performing the service request.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050003
Database table does not exist.

Category:
Programmatic

Cause:
An error was encountered while performing a database activity.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050004
Cannot bind all parameters in query {0}.

Category:
Programmatic

Cause:
An error was encountered while creating the SQL query. The number of parameters required was inconsistent with the number of parameters provided.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050005
Unable to initialize the database {0}.

Category:
Programmatic

Cause:
An error was encountered while the system was initializing the database connections.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050006
Unable to create database connection for {0}.

Category:
Programmatic

Cause:
An error was encountered while trying to create a database connection for the named server instance.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050007
Server busy. Unable to obtain a connection to the database.

Category:
Programmatic

Cause:
The server was unable to establish a connection to the database.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050008
Unable to execute query {0}.

Category:
Programmatic

Cause:
An error was encountered while executing the specified query.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050009
Unable to execute callable query {0}.

Category:
Programmatic

Cause:
An error was encountered while executing the named callable query.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050010
Unable to create the result set for query {0}.

Category:
Programmatic

Cause:
An error was encountered while creating the results for the specified query.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050011
Unable to execute SQL statement {0}.

Category:
Programmatic

Cause:
An error was encountered while executing the given SQL statement.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050012
Unable to determine the database type.

Category:
Programmatic

Cause:
An error was encountered while determining the database type.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050013
Error occurred while closing connection: ({0}).

Category:
Programmatic

Cause:
An error was encountered while closing the database connection.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050014
Cannot begin the transaction. JDBC Error:

Category:
Programmatic

Cause:
An error was encountered while beginning a database transaction.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050015
Cannot commit the transaction. JDBC Error:

Category:
Programmatic

Cause:
An error was encountered while committing a database transaction.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050016
Failed to find indexable webviewable for content item {0} with revlabel {1} and dID {2}.

Category:
Programmatic

Cause:
An error was encountered while indexing the specified content item.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050017
Text conversion of the file {0} failed.

Category:
Programmatic

Cause:
An error was encountered while indexing the specified content item.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050018
Indexing failed.

Category:
Programmatic

Cause:
An error was encountered while indexing the specified content item.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050019
The creation date ({0}) of the new revision is not later than the creation date ({1}) of the latest revision in the system.

Category:
Programmatic

Cause:
An error was encountered while importing the content item. The create date for the new revision must be later than the older revision.

Action:
The Archiver uses dates to validate the correct order of revisions. By default, it uses the dCreateDate, but this can be configured to use the dInDate by setting the configuration parameter UseRevisionCreateDate to true.

UCM-CS-050020
The release date ({0}) of the new revision is not later than the release date ({1}) of the latest revision in the system.

Category:
Programmatic

Cause:
An error was encountered while importing the content item. The in date for the new revision must be later than the older revision.

Action:
The Archiver uses dates to validate the correct order of revisions. By default, it uses the dCreateDate, but this can be configured to use the dInDate by setting the configuration parameter UseRevisionCreateDate to true.

UCM-CS-050021
Oracle WebCenter Content failed to initialize inside its servlet environment.

Category:
Programmatic

Cause:
An error was encountered during initialization of the servlet environment./td>

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050022
Active index ({0}) is not valid for the indexer engine ({1}).

Category:
Programmatic

Cause:
The currently active search index was invalid for the configured indexer engine.

Action:
A rebuild of the search collection is required.

UCM-CS-050023
An error occurred during indexing.

Category:
Programmatic

Cause:
The system encountered an error while indexing a document.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050024
Search collection is not up-to-date.

Category:
Programmatic

Cause:
The system has determined that the search indexing collection configuration has been modified.

Action:
A rebuild of the search collection is recommended.

UCM-CS-050025
Commit is called by thread {0} in auto-commit mode.

Category:
Programmatic

Cause:
A database commit call was made in a thread configured to be in auto-commit mode.

Action:
The stack trace can be examined to determine which component or feature tried to perform the commit.

UCM-CS-050026
Database running out of tablespace

Category:
Programmatic

Cause:
The database system is running out of tablespace.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050027
Possible database connection failure encountered. Error message: ({0}).

Category:
Programmatic

Cause:
The system has encountered a database connection failure.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-050028
Unable to create database connection for the database {0} with connection string {1}. Please make sure that the connection string, user and password are correct.

Category:
Programmatic

Cause:
The system has encountered an issue with creating a database connection.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entries that are part of this message stack.

UCM-CS-060000
Starting the service {0} version {1} PID {2}.

Category:
Configuration

Cause:

Action:

UCM-CS-060001
{0} component, version {1}, provides {2} feature(s)

Category:
Configuration

Cause:

Action:

UCM-CS-060002
Server ready and waiting for connection on port {1}.

Category:
Configuration

Cause:

Action:

UCM-CS-060003
Event generated by user {0} at host {1}.

Category:
Configuration

Cause:

Action:

UCM-CS-060004
User {0} changed the following entry in config.cfg on server {1}:

Category:
Configuration

Cause:

Action:

UCM-CS-060005
Restarting rebuild of the search index.

Category:
Programmatic

Cause:

Action:

UCM-CS-060006
Starting rebuild of the search index.

Category:
Programmatic

Cause:

Action:

UCM-CS-060007
Finished rebuilding the search index with a total of {0} files successfully indexed. A total of {1} files had a full text index.

Category:
Programmatic

Cause:

Action:

UCM-CS-060008
Finished rebuilding the search index with a total of {0} files successfully indexed. A total of {1} files had a full text index and {2} failed to index.

Category:
Programmatic

Cause:

Action:

UCM-CS-060009
Indexing aborted.

Category:
Programmatic

Cause:

Action:

UCM-CS-060010
Text index {0} is optimized.

Category:
Programmatic

Cause:

Action:

UCM-CS-060011
Started monitoring.

Category:
Programmatic

Cause:

Action:

UCM-CS-060012
Event {0} has finished

Category:
Programmatic

Cause:

Action:

UCM-CS-060013
Shutting down server connections.

Category:
Programmatic

Cause:

Action:

UCM-CS-060014
Trace is verbose.

Category:
Programmatic

Cause:

Action:

UCM-CS-060015
Trace sections list has been updated to {0}.

Category:
Programmatic

Cause:

Action:

UCM-CS-060016
Referred to by {0}.\&lf;

Category:
Files

Cause:

Action:

UCM-CS-060017
User agent is {0} and request method is {1}.\&lf;

Category:
Files

Cause:

Action:

UCM-CS-060018
The refresh activity '{0}' has completed {1} out of {2} links with {3} errors.

Category:
Programmatic

Cause:

Action:

UCM-CS-060019
The fsconfig.hda file has been created in the data/filestore/config directory.

Category:
Configuration

Cause:

Action:

UCM-CS-060020
Added:

Category:
Configuration

Cause:

Action:

UCM-CS-060021
Modified:

Category:
Configuration

Cause:

Action:

UCM-CS-060022
Removed:

Category:
Configuration

Cause:

Action:

UCM-CS-060023
Trace is not verbose.

Category:
Programmatic

Cause:

Action:

UCM-CS-100001
Oracle WebCenter Capture URL has not been configured. Please contact the Administrator.

Category:
Configuration

Cause:
ODDCURLPath environment variable is not set.

Action:
Set the ODDCURLPath to point to ODDC server.

UCM-CS-100002
Unable to detach Oracle WebCenter Content document from siebel entity.

Category:
Data

Cause:
Database delete operation failed since the row does not exist if the document is already detached.

Action:
Refresh the Managed Attachments window.

UCM-CS-100003
Error: siebelEntityField and siebelEntityValue are mandatory Parameters.

Category:
Programmatic

Cause:
One of the parameters SiebeleEntityField OR SiebeleEntittyValue is missing.

Action:
Make sure the URL has the parameters SiebeleEntityField AND SiebeleEntittyValue.

UCM-CS-100101
User '{0}' does not have sufficient access privileges to perform this operation. Access privileges may have expired, requiring the user to re-select Managed Attachments from the Oracle E-Business Suite Zoom Menu.

Category:
Configuration

Cause:
User does not have sufficient access privileges to perform this operation. Access privileges may have expired.

Action:
Contact Administrator for getting appropriate Roles for Access. User needs to re-select Managed Attachments from the Oracle E-Business Suite Zoom Menu.

UCM-CS-100102
Failed to detach document '{0}'

Category:
Data

Cause:
Document detach operation failed because the document is already detached or deleted.

Action:
Refresh Managed Attachments page and try this operation again.

UCM-CS-100103
User '{0}' does not have sufficient access privileges to perform this operation. Access privileges may have expired, requiring the user to re-access Managed Attachments from the PeopleSoft User Interface.

Category:
Configuration

Cause:
User does not have sufficient access privileges to perform this operation. Access privileges may have expired.

Action:
Contact Administrator for getting appropriate Roles for Access. User needs to re-select Managed Attachments from the Oracle E-Business Suite Zoom Menu.

UCM-CS-800001
Cannot load archive.

Category:
Error

Cause:
Cannot load archive.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800002
Cannot build archive.

Category:
Error

Cause:
Cannot build archive.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800003
No value was provided and no default value is set for the metadata field

Category:
Error

Cause:
No value was provided and no default value is set for the metadata field

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800004
The form '{0}' already contains a field named '{1}'.

Category:
Error

Cause:
The form already contains a field of the same name.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800005
Dashboard error occured while saving as new dashboard

Category:
Error

Cause:
Dashboard error occured while saving as new dashboard

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800006
Workflow approve action does not work for non-existent item.

Category:
Error

Cause:
Workflow approve action does not work for non-existent item.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800007
Unable to load from RSS URL location. Check RSS dashboard options in edit view.

Category:
Error

Cause:
Unable to load from RSS URL location. Check RSS dashboard options in edit view.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800008
Unable to update the configuration information.

Category:
Error

Cause:
Unable to update the configuration information.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800009
Unable to update the data source information.

Category:
Error

Cause:
Unable to update the data source information.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800010
Unable to export the report type xml data.

Category:
Error

Cause:
Unable to export the report type xml data.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800011
Unable to check in report.

Category:
Error

Cause:
Unable to check in report.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800012
Unable to run the scheduled report.

Category:
Error

Cause:
Unable to run the scheduled report.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800013
Unable to checkout default reports.

Category:
Error

Cause:
Unable to checkout default reports.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800014
The report template is missing.

Category:
Error

Cause:
The report template is missing.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800015
Unable to get the service data source parameters.

Category:
Error

Cause:
Unable to get the service data source parameters.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800016
Unable to get the query data source parameters.

Category:
Error

Cause:
Unable to get the query data source parameters.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800017
The BL Publisher RTF processor failed.

Category:
Error

Cause:
The BL Publisher RTF processor failed.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800018
Unable to get the related content.

Category:
Error

Cause:
Unable to get the related content.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800019
Unable to get the related content types.

Category:
Error

Cause:
Unable to get the related content types.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800020
The related type ID is missing.

Category:
Error

Cause:
The related type is missing a field.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800021
The related type name '{0}' does not exist.

Category:
Error

Cause:
The related type name does not exist.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800022
The related type name '{0}' already exists.

Category:
Error

Cause:
The related type name already exists.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800023
The related type class ID is missing.

Category:
Error

Cause:
The related type class ID is missing.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800024
The supersede related type cannot be edited. Related content currently exists.

Category:
Error

Cause:
The supersede related type cannot be edited. Related content currently exists.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800025
The content ID (dID) is missing.

Category:
Error

Cause:
The content ID is missing.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800026
No external sources were found. Check to see if the 'ExternalHelper' component is installed and enabled.

Category:
Error

Cause:
No external sources were found. Check to see if the 'ExternalHelper' component is installed and enabled.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800027
More than one superseded content links selected. Please remove excess superseded links.

Category:
Error

Cause:
More than one superseded content links selected. Please remove excess superseded links.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800028
URMAgent or RetentionManager components are disabled. Please click ok to enable the components. Then, restart the server and configure UrmAgent source.

Category:
Error

Cause:
URMAgent or RetentionManager components are disabled. Please click ok to enable the components. Then, restart the server and configure UrmAgent source.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800029
{0} disposition action is not defined in DispositionActionsList

Category:
Error

Cause:
Disposition Action is not specified for this dDispostion.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800030
Error while checking setup requirements for new component install.

Category:
Error

Cause:
Error while checking setup requirements for new component install.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800031
Cannot checkout content item: Not Revisionable.

Category:
Error

Cause:
Cannot checkout content item: Not Revisionable.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800032
Cannot edit content item: Not Editable.

Category:
Error

Cause:
Cannot edit content item: Not Editable.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800033
Cannot delete content item: Not Deletable.

Category:
Error

Cause:
Cannot delete content item: Not Deletable.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800034
User does not have access to folders(or parent folders) or folder does not exists.

Category:
Error

Cause:
User does not have access to folders(or parent folders) or folder does not exists.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800035
Error retrieving information about category '{0}'

Category:
Error

Cause:
Error retrieving information about the category

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800036
Error retrieving information about folder '{0}'

Category:
Error

Cause:
Error retrieving information about the folder

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800037
Error retrieving information about series '{0}'

Category:
Error

Cause:
Error retrieving information about the series

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800038
Error creating category named '{0}': category with specified id exists

Category:
Error

Cause:
Error creating item, item with specified id exists

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800039
Unable to get screening results for categories

Category:
Error

Cause:
Unable to get screening results

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800040
Unable to prepare the HDA edit form.

Category:
Error

Cause:
Unable to prepare the HDA edit form.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800041
Unable to notify pending event actions

Category:
Error

Cause:
Unable to notify pending event actions

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800042
Unable to Mark Reviewed

Category:
Error

Cause:
Unable to Mark Reviewed

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800043
Unable to supersede content or records.

Category:
Error

Cause:
Unable to supersede content or records.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800044
Access denied - cutoff items are readonly

Category:
Error

Cause:
Access denied - cutoff items are readonly

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800045
Failed to delete metadata history.

Category:
Error

Cause:
Failed to delete metadata history.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800046
Disposition contains unprocessed content or record.

Category:
Error

Cause:
Disposition contains unprocessed content or record.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800047
Unable to find log or report information.

Category:
Error

Cause:
Unable to find log or report information.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800048
Failed to process report.

Category:
Error

Cause:
Failed to process report.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800049
Cannot edit frozen content or folder

Category:
Error

Cause:
Cannot edit frozen content or folder

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800050
Unable to run batch services for notifications

Category:
Error

Cause:
Unable to run batch services

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800051
Unable to list scheduled freezes

Category:
Error

Cause:
Unable to list scheduled freezes

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800052
Cannot delete frozen content.

Category:
Error

Cause:
Cannot delete frozen content.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800053
Unable to Notify Process Monitoring Alerts

Category:
Error

Cause:
Unable to Notify Process Monitoring Alerts

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800054
Unable to reset performance process monitoring

Category:
Error

Cause:
Unable to reset performance process monitoring

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800055
Unable to reset performance process monitoring alerts

Category:
Error

Cause:
Unable to reset performance process monitoring alerts

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800056
Unable to parse category dispositions information

Category:
Error

Cause:
Unable to parse category dispositions information

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800057
The field {0} requires an integer entry.

Category:
Error

Cause:
The field requires an integer entry.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800058
System derived cutoff must be first action

Category:
Error

Cause:
System derived cutoff must be first action

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800059
Invalid Trigger Event: first disposition rule has no preceding action

Category:
Error

Cause:
Invalid Trigger Event: first disposition rule has no preceding action

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800060
Delete Revision action is forbidden in permanent categories

Category:
Error

Cause:
Delete Revision action is forbidden in permanent categories

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800061
Destroy or Delete Revision action is forbidden in permanent categories

Category:
Error

Cause:
Destroy or Delete Revision action is forbidden in permanent categories

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800062
Destroy action is forbidden in permanent categories

Category:
Error

Cause:
Destroy action is forbidden in permanent categories

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800063
The first character of the Name field must be alphabetic

Category:
Error

Cause:
The first character of the Name field must be alphabetic

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800064
The Name field contains invalid character

Category:
Error

Cause:
The Name field contains invalid character

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800065
User does not have all matching Supplemental Markings.

Category:
Error

Cause:
User does not have all matching Supplemental Markings.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800066
User does not have Security Markings.

Category:
Error

Cause:
User does not have Security Markings.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800067
User does not have group(alias)/user permissions (ACL-based collaboration security privilege).

Category:
Error

Cause:
User does not have group(alias)/user permissions (ACL-based collaboration security privilege).

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800068
Performance process monitoring time exceeded max limit

Category:
Error

Cause:
Performance process monitoring time exceeded max limit

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800069
This class can only contain classes

Category:
Error

Cause:
This class can only contain classes

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800070
This class can only contain files

Category:
Error

Cause:
This class can only contain files

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800071
This class can only contain content items (or volumes)

Category:
Error

Cause:
This class can only contain content items (or volumes)

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800072
This class can contain classes, files, or content items

Category:
Error

Cause:
This class can contain classes, files, or content items

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800073
This file can only contain sub-files

Category:
Error

Cause:
This file can only contain sub-files

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800074
This file can only contain content items (or volumes)

Category:
Error

Cause:
This file can only contain content items (or volumes)

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800075
This file can contain sub-files or content items

Category:
Error

Cause:
This file can contain sub-files or content items

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800076
This sub-file can only contain content items (or volumes)

Category:
Error

Cause:
This sub-file can only contain content items (or volumes)

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800077
This volume can only contain content items

Category:
Error

Cause:
This volume can only contain content items

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800078
There was an internal error in submitting the form

Category:
Error

Cause:
There was an internal error in submitting the form

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800079
There was an internal error in reseting the form

Category:
Error

Cause:
There was an internal error in reseting the form

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800080
Error initiating connection or retrieving HTTP response code.

Category:
Error

Cause:
Error initiating connection or retrieving HTTP response code.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800081
Unable to get response stream from HTTP request.

Category:
Error

Cause:
Unable to get response stream from HTTP request.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800082
Http request needs a response rule to be specified is requesting agent a browser or an application

Category:
Error

Cause:
Http request needs a response rule to be specified is requesting agent a browser or an application

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800083
Unable to initiate connection.

Category:
Error

Cause:
Unable to initiate connection.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800084
The connection is currently not available.

Category:
Error

Cause:
The connection is currently not available.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800085
Credential map data was not successfully loaded.

Category:
Error

Cause:
Credential map data was not successfully loaded.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800086
Credentials map table {0} is missing.

Category:
Error

Cause:
Credentials map table is missing.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800087
Error creating charge type '{0}'.

Category:
Error

Cause:
Error creationg charge type.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800088
Error editing charge type '{0}'.

Category:
Error

Cause:
Error editing charge type.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800089
Error deleting charge type '{0}'.

Category:
Error

Cause:
Error deleting charge type.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800090
Error retrieving information about charge type '{0}'.

Category:
Error

Cause:
Error retrieving information about charge type.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800091
Charge type '{0}' already exists.

Category:
Error

Cause:
Error creating charge type: charge type with specified id exists. Charge type already exists.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack. Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800092
Invalid adjustment amount. Adjustment amount cannot make the invoice amount less than zero.

Category:
Error

Cause:
Invalid adjustment amount. Adjustment amount cannot make the invoice amount less than zero.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800093
Error creating payment type '{0}'.

Category:
Error

Cause:
Error creationg payment type.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800094
Error editing payment type '{0}'.

Category:
Error

Cause:
Error editing payment type.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800095
Error deleting payment type '{0}'.

Category:
Error

Cause:
Error deleting payment type.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800096
Error retrieving information about payment type '{0}'.

Category:
Error

Cause:
Error retrieving information about payment type.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800097
Payment type '{0}' already exists.

Category:
Error

Cause:
Error creating payment type: charge type with specified id exists. Payment type already exists.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack. Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800098
Error creating customer '{0}'.

Category:
Error

Cause:
Error creationg customer.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800099
Error editing customer '{0}'.

Category:
Error

Cause:
Error editing customer.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800100
Error deleting customer '{0}'.

Category:
Error

Cause:
Error deleting customer.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800101
Error retrieving information about customer '{0}'.

Category:
Error

Cause:
Error retrieving information about customer.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800102
Customer '{0}' already exists.

Category:
Error

Cause:
Error creating customer: customer with specified id exists.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800103
Payment type '{0}' already exists.

Category:
Error

Cause:
Error creating payment type: charge type with specified id exists. Payment type already exists.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack. Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800104
Charge type '{0}' already exists.

Category:
Error

Cause:
Error creating charge type: charge type with specified id exists. Charge type already exists.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack. Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800105
Error creating charge transaction '{0}'.

Category:
Error

Cause:
Error creating charge transaction.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800106
Error browsing charge transactions for invoice '{0}'.

Category:
Error

Cause:
Error browsing charge transactions.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800107
Object Type is missing. You must provide an object type for charges with actions (Creation, Destruction or Reservation).

Category:
Error

Cause:
Object Type is missing. You must provide an object type for charges with actions (Creation, Destruction or Reservation).

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800108
Invalid object type. The charge types object type does not match the external items object type

Category:
Error

Cause:
Invalid object type. The charge types object type does not match the external items object type

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800109
Invalid media type. The charge types media type does not match the external items media type

Category:
Error

Cause:
Invalid media type. The charge types media type does not match the external items media type

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800110
Invalid external item. The specific external item does not exist.

Category:
Error

Cause:
Invalid external item. The specific external item does not exist.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800111
Cannot delete a paid transaction.

Category:
Error

Cause:
Cannot delete a paid transaction.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800112
Unable to retrieve transaction results.

Category:
Error

Cause:
Unable to retrieve transaction results.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800113
External Item is missing. You must provide an ID or Name for the external item you wish to add a transaction for.

Category:
Error

Cause:
External Item is missing. You must provide an ID or Name for the external item you wish to add a transaction for.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800114
Must select one or more charge periods for calculation and indicate a number for charge increments. (Days, Weeks, etc).

Category:
Error

Cause:
Must select one or more charge periods for calculation and indicate a number for charge increments. (Days, Weeks, etc).

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800115
Must indicate a number for charge increments for each selected charge period.

Category:
Error

Cause:
Must indicate a number for charge increments for each selected charge period.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800116
Must select a department client for processing.

Category:
Error

Cause:
Must select a department client for processing.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800117
Error Processing Storage Charges.

Category:
Error

Cause:
Error Processing Storage Charges.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800118
Cannot delete charge type '{0}' is being used by charge transactions.

Category:
Error

Cause:
Cannot delete charge type, it is being used by charge transactions.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800119
Cannot delete customer '{0}' is being used by charge invoices.

Category:
Error

Cause:
Cannot delete customer, they are is being used by charge invoices.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800120
Error creating storage item.

Category:
Error

Cause:
Error creating storage item.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800121
Error deleting storage '{0}'

Category:
Error

Cause:
Error deleting storage item.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800122
Storage item is unavailable

Category:
Error

Cause:
Storage item is unavailable

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800123
Storage item is blocked

Category:
Error

Cause:
Storage item is blocked

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800124
Storage item is reserved

Category:
Error

Cause:
Storage item is reserved

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800125
Storage '{0}' is not empty.

Category:
Error

Cause:
Storage item is not empty.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800126
Unable to block storage item(s). One or more storage item(s) contains an external content item(s).

Category:
Error

Cause:
Unable to block storage item(s). One or more storage item(s) contains an external content item(s).

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800127
Unable to reserve storage item(s). One or more storage item(s) contains an external content item(s) or is reserved.

Category:
Error

Cause:
Unable to reserve storage item(s). One or more storage item(s) contains an external content item(s) or is reserved.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800128
Unable to delete storage item(s). One or more storage item(s) contains an external content item(s).

Category:
Error

Cause:
Unable to delete storage item(s). One or more storage item(s) contains an external content item(s).

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800129
Error updating storage availability.

Category:
Error

Cause:
Error updating storage availability.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800130
Unable to get storage items for export.

Category:
Error

Cause:
Unable to get storage items for export.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800131
Error editing storage types.

Category:
Error

Cause:
Error editing storage types.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800132
Error retrieving information about storage type '{0}'.

Category:
Error

Cause:
Error retrieving information about storage type.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800133
Error creating storage type '{0}': storage type with specified id exists.

Category:
Error

Cause:
Error creating storage type: storage type with specified id exists.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800134
Error creating object type '{0}': object type with specified id exists.

Category:
Error

Cause:
Error creating object type: object type with specified id exists.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800135
Object Type is Linked to another object type.

Category:
Error

Cause:
Object Type is Linked to another object type.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800136
Error creating media type '{0}': media type with specified id exists.

Category:
Error

Cause:
Error creating media type: media type with specified id exists.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800137
Media type '{0}' is being used by external content.

Category:
Error

Cause:
Media type is being used by external content.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800138
Error editing request.

Category:
Error

Cause:
Error editing request.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800139
Cannot complete requests that have not been processed

Category:
Error

Cause:
Cannot complete requests that have not been processed

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800140
Cannot update a checked out request with any other status than completed

Category:
Error

Cause:
Cannot update a checked out request with any other status than completed

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800141
Cannot update a non-processed request with status of returned

Category:
Error

Cause:
Cannot update a non-processed request with status of returned

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800142
Check out date cannot be less than request date

Category:
Error

Cause:
Check out date cannot be less than request date

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800143
Error rejecting reservation items.

Category:
Error

Cause:
Error rejecting reservation items.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800144
Error processing reservation content workflow.

Category:
Error

Cause:
Error processing reservation content workflow.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800145
Unable to get reservation items for export.

Category:
Error

Cause:
Unable to get reservation items for export.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800146
The external item is already pending or checked out.

Category:
Error

Cause:
The external item is already pending or checked out.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800147
Record already checked out with another item. Cannot check this item out at this time.

Category:
Error

Cause:
Record already checked out with another item. Cannot check this item out at this time.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800148
Notify Requestors of Overdue Requests

Category:
Error

Cause:
Notify Requestors of Overdue Requests

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800149
Item duplicated within request. Item maybe contained within another requested item.

Category:
Error

Cause:
Item duplicated within request. Item maybe contained within another requested item.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800150
Failed to check in content item for reservation.

Category:
Error

Cause:
Failed to check in content item for reservation.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800151
Requested item has been destroyed. Cannot reserve.

Category:
Error

Cause:
Requested item has been destroyed. Cannot reserve.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800152
Reservation items belonging to this group still exist in the system.

Category:
Error

Cause:
Reservation items belonging to this group still exist in the system.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800153
The external item '{0}' does not exist.

Category:
Error

Cause:
The external item does not exist.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800154
Item inside of a non record container must be a non record

Category:
Error

Cause:
Item inside of a non record container must be a non record

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800155
Access denied by manager

Category:
Error

Cause:
Access denied by manager

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800156
An error occurred writing the audit.

Category:
Error

Cause:
An error occurred writing the audit.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800157
Not authorized to perform action.

Category:
Error

Cause:
Not authorized to perform action.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800158
Error processing user label.

Category:
Error

Cause:
Error processing user label.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800159
Error processing storage label.

Category:
Error

Cause:
Error processing storage label.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800160
Unable to get user label.

Category:
Error

Cause:
Unable to get user label.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800161
There are no users selected that contain barcode values. Cannot print labels.

Category:
Error

Cause:
There are no users selected that contain barcode values. Cannot print labels.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800162
There is no user(s) selected to print barcode labels for. Please select/input user(s) to print barcodes for.

Category:
Error

Cause:
There is no user(s) selected to print barcode labels for. Please select/input user(s) to print barcodes for.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800163
Content items location does not match the storage location being imported.

Category:
Error

Cause:
Content items location does not match the storage location being imported.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800164
Error moving storage item, cannot move storage items into 'Other' type storage items

Category:
Error

Cause:
Error moving storage item, cannot move storage items into 'Other' type storage items

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800165
Error moving storage item, cannot move storage items of type 'Root'.

Category:
Error

Cause:
Error moving storage item, cannot move storage items of type 'Root'.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800166
Error moving storage item, cannot move storage items of type 'Other'.

Category:
Error

Cause:
Error moving storage item, cannot move storage items of type 'Other'.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800167
Error moving storage item, storage item already exists within the selected storage item.

Category:
Error

Cause:
Error moving storage item, storage item already exists within the selected storage item.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800168
Error moving storage item, cannot move storage item into itself.

Category:
Error

Cause:
Error moving storage item, cannot move storage item into itself.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800169
There is a badly defined table element in the web form. The block has been defined as repeating, but it has no table assigned to it.

Category:
Error

Cause:
There is a badly defined table element in the web form. The block has been defined as repeating, but it has no table assigned to it.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800170
Encountered an unexpected end of the table. Cannot find close for repeat block.

Category:
Error

Cause:
Encountered an unexpected end of the table. Cannot find close for repeat block.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800171
An unmatched closing tag was encountered. The advanced element {0} is not properly closed by {1}.

Category:
Error

Cause:
An unmatched closing tag was encountered. The advanced element is not properly closed.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800172
An IO error was encountered during the generation of the web form.

Category:
Error

Cause:
An IO error was encountered during the generation of the web form.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800173
There is no content for the web form file.

Category:
Error

Cause:
There is no content for the web form file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800174
Unable to access native web form file.

Category:
Error

Cause:
Unable to access native web form file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800175
Content '{0}' file name does not match with previous revisions.

Category:
Error

Cause:
Content file name does not match with previous revisions.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800176
Unable to access system folders.

Category:
Error

Cause:
Unable to access system folders.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800177
Unable to force security on moved folder or content.

Category:
Error

Cause:
Unable to force security on moved folder or content.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800178
Unable to retrieve folder information.

Category:
Error

Cause:
Unable to retrieve folder information.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800179
Unable to retrieve folder.

Category:
Error

Cause:
Unable to retrieve folder.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800180
Unable to update columns.

Category:
Error

Cause:
Unable to update columns.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800181
Unable to retrieve columns.

Category:
Error

Cause:
Unable to retrieve columns.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800182
Unable to retrieve administration configuration.

Category:
Error

Cause:
Unable to retrieve administration configuration.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800183
Unable to update administration configuration.

Category:
Error

Cause:
Unable to update administration configuration.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800184
Virtual folder name specifies invalid characters.

Category:
Error

Cause:
Virtual folder name specifies invalid characters.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800185
Unable to move items.

Category:
Error

Cause:
Unable to move items.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800186
Unable to delete items.

Category:
Error

Cause:
Unable to delete items.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800187
Unable to copy items.

Category:
Error

Cause:
Unable to copy items.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800188
Unable to create shortcut.

Category:
Error

Cause:
Unable to create shortcut.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800189
Unable to create virtual folder.

Category:
Error

Cause:
Unable to create virtual folder.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800190
Unable to display virtual folder information.

Category:
Error

Cause:
Unable to display virtual folder information.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800191
Unable to update virtual folder.

Category:
Error

Cause:
Unable to update virtual folder.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800192
Unable to remove all content.

Category:
Error

Cause:
Unable to remove all content.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800193
Unable to restore items.

Category:
Error

Cause:
Unable to restore items.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800194
Unable to retrieve specified fields.

Category:
Error

Cause:
Unable to retrieve specified fields.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800195
Unable to update specified fields.

Category:
Error

Cause:
Unable to update specified fields.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800196
Unable to retrieve specified field defaults.

Category:
Error

Cause:
Unable to retrieve specified field defaults.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800197
Unable to update specified field defaults.

Category:
Error

Cause:
Unable to update specified field defaults.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800198
Unable to retrieve specified virtual folder.

Category:
Error

Cause:
Unable to retrieve specified virtual folder.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800199
Unable to update specified virtual folder.

Category:
Error

Cause:
Unable to update specified virtual folder.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800200
Unable to edit specified virtual folder.

Category:
Error

Cause:
Unable to edit specified virtual folder.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800201
Unable to display virtual folder information.

Category:
Error

Cause:
Unable to display virtual folder information.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800202
Unable to open folder.

Category:
Error

Cause:
Unable to open folder.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800203
Unable to get reference.

Category:
Error

Cause:
Unable to get reference.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800204
Unable to move, destination is a subfolder.

Category:
Error

Cause:
Unable to move, destination is a subfolder.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800205
Unable to add shortcut.

Category:
Error

Cause:
Unable to add shortcut.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800206
Unable to move shortcut.

Category:
Error

Cause:
Unable to move shortcut.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800207
Unable to copy shortcut.

Category:
Error

Cause:
Unable to copy shortcut.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800208
Reference is a ancestor of shortcut.

Category:
Error

Cause:
Reference is a ancestor of shortcut.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800209
Unable to load environment.

Category:
Error

Cause:
Unable to load environment.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800210
Unable to change login

Category:
Error

Cause:
Unable to change login

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800211

Category:
Error

Cause:
Local Folder and Directory already specified.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800212

Category:
Error

Cause:
Directory not empty.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800213
Unable to archive.

Category:
Error

Cause:
Unable to archive.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800214
The folder structure is locked.

Category:
Error

Cause:
The folder structure is locked.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800215
This folder cannot currently be changed.

Category:
Error

Cause:
This folder cannot currently be changed.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800216
Search Name could not be found

Category:
Error

Cause:
Search Name could not be found

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800217
Search text could not be found for validation

Category:
Error

Cause:
Search text could not be found for validation

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800218
Cannot perform an empty search

Category:
Error

Cause:
Cannot perform an empty search

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800219
SES does not support left-truncated wildcards

Category:
Error

Cause:
SES does not support left-truncated wildcards

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800220
SES does not support different criteria conjunctions

Category:
Error

Cause:
SES does not support different criteria conjunctions

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800221
SES does not support the '{0}' operator

Category:
Error

Cause:
SES does not support that operator

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800222
Permission denied to freeze federated items

Category:
Error

Cause:
Permission denied to freeze federated items

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800223
Archive does not contain a file for item '{0}'

Category:
Error

Cause:
Archive does not contain a file for that item

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800224
'xCategoryID' and 'xFolderID' cannot both be specified for item '{0}'

Category:
Error

Cause:
'xCategoryID' and 'xFolderID' cannot both be specified for the item

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800225
Cannot assign folder IDs to a non-record for item '{0}'

Category:
Error

Cause:
Cannot assign folder IDs to a non-record for the item

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800226
Cannot edit frozen item

Category:
Error

Cause:
Cannot edit frozen item

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800227
Cannot delete frozen item

Category:
Error

Cause:
Cannot delete frozen item

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800228
Cannot delete frozen item or item is in frozen folders.

Category:
Error

Cause:
Cannot delete frozen item or item is in frozen folders.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800229
The external item was successfully deleted

Category:
Error

Cause:
The external item was successfully deleted

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800230
Unable to get external item information.

Category:
Error

Cause:
Unable to get external item information.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800231
Unable to get external batch status details information.

Category:
Error

Cause:
Unable to get external batch status details information.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800232
Unable to reset external batch status information.

Category:
Error

Cause:
Unable to reset external batch status information.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800233
Notify External Batch Status Alerts

Category:
Error

Cause:
Notify External Batch Status Alerts

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800234
Unable to run external report

Category:
Error

Cause:
Unable to run external report

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800235
Error checking or creating WebDAV locks cache file.

Category:
Error

Cause:
Error checking or creating WebDAV locks cache file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800236
Not allowed to lock this folder through WebDAV.

Category:
Error

Cause:
Not allowed to lock this folder through WebDAV.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800237
Unable to perform lock. Lock request did not send owner information.

Category:
Error

Cause:
Unable to perform lock. Lock request did not send owner information.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800238
Unable to lock file. All locks must be requested as exclusive.

Category:
Error

Cause:
Unable to lock file. All locks must be requested as exclusive.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800239
Unable to lock file. Bad request.

Category:
Error

Cause:
Unable to lock file. Bad request.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800240
Unable to undo checkout during lock cleaning cycle.

Category:
Error

Cause:
Unable to undo checkout during lock cleaning cycle.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800241
The requested location does not exist.

Category:
Error

Cause:
The requested location does not exist.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800242
Infinity is not allowed. Please upgrade your web filter and restart the Content Server.

Category:
Error

Cause:
Infinity is not allowed. Please upgrade your web filter and restart the Content Server.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800243
Unable to lock file at this path. Please use the tip-revision path.

Category:
Error

Cause:
Unable to lock file at this path. Please use the tip-revision path.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800244
Unable to unlock file at this path. Please use the tip-revision path.

Category:
Error

Cause:
Unable to unlock file at this path. Please use the tip-revision path.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800245
Unable to put file at this path. Please only use the tip-revision path of an existing file.

Category:
Error

Cause:
Unable to put file at this path. Please only use the tip-revision path of an existing file.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800246
Unable to delete file at this path. Please use the tip-revision path.

Category:
Error

Cause:
Unable to delete file at this path. Please use the tip-revision path.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800247
Could not send WebDAV XML to client.

Category:
Error

Cause:
Could not send WebDAV XML to client.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800248
Error getting owner from lock {0}. Please ensure that your XML libraries are properly installed.

Category:
Error

Cause:
Error getting owner from lock. Please ensure that your XML libraries are properly installed.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800249
Could not parse incoming WebDAV XML request.

Category:
Error

Cause:
Could not parse incoming WebDAV XML request.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800250
Could not create WebDAV input stream from the DataBinder.

Category:
Error

Cause:
Could not create WebDAV input stream from the DataBinder.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800251
Could not get bytes from input stream.

Category:
Error

Cause:
Could not get bytes from input stream.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800252
Folio item {0} not found

Category:
Error

Cause:
Folio item not found

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800253
Could not write folio {0}

Category:
Error

Cause:
Could not write folio

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800254
Unable to save changes.

Category:
Error

Cause:
Unable to save changes.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800255
Unable to edit folio template.

Category:
Error

Cause:
Unable to edit folio template.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800256
Unable to create new folio.

Category:
Error

Cause:
Unable to create new folio.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800257
Unable to create new folio template.

Category:
Error

Cause:
Unable to create new folio template.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800258
Unable to create new template folio.

Category:
Error

Cause:
Unable to create new template folio.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800259
Unable to load folio node.

Category:
Error

Cause:
Unable to load folio node.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800260
Unable to load temporary folio node.

Category:
Error

Cause:
Unable to load temporary folio node.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800261
Unable to load folio edit page.

Category:
Error

Cause:
Unable to load folio edit page.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800262
Unable to generate unique ids.

Category:
Error

Cause:
Unable to generate unique ids.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800263
Unable to create folio snapshot.

Category:
Error

Cause:
Unable to create folio snapshot.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800264
Unable to lock folio.

Category:
Error

Cause:
Unable to lock folio.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800265
Unable to load archived folio.

Category:
Error

Cause:
Unable to load archived folio.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800266
Previous revision of the folio does not exist.

Category:
Error

Cause:
Previous revision of the folio does not exist.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800267
Unable to checkin archived folio item.

Category:
Error

Cause:
Unable to checkin archived folio item.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800268
Unable to create folio from basket.

Category:
Error

Cause:
Unable to create folio from basket.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800269
Unable to clone folio.

Category:
Error

Cause:
Unable to clone folio.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800270
Folio parent node data missing.

Category:
Error

Cause:
Folio parent node data missing.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800271
This service cannot edit folio templates.

Category:
Error

Cause:
This service cannot edit folio templates.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800272
Could not add folio to archive.

Category:
Error

Cause:
Could not add folio definition to archive.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800273
Unable to edit locked folio.

Category:
Error

Cause:
Unable to edit locked folio.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800274
Error indexing folio links.

Category:
Error

Cause:
Error indexing folio links.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800275
Declassify On Date is not a valid date

Category:
Error

Cause:
Declassify On Date is not a valid date

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800276
Publication Date is not a valid date

Category:
Error

Cause:
Publication Date is not a valid date

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800277
Failed to check in '{0}' freeze audit information. Please reference '{1}' audit log.

Category:
Error

Cause:
Failed to check in freeze audit information. Please reference audit log.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800278
Unable to run disposition action.

Category:
Error

Cause:
Unable to run disposition action.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800279
Installing the RelatedContent component...

Category:
Error

Cause:
Installing the RelatedContent component...

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

UCM-CS-800280
Offsite FTP cannot change to the directory '{0}'. Please make sure it exists on the FTP site.

Category:
Error

Cause:
Offsite FTP cannot change direcotry.

Action:
Details are usually given in the cause exception. Look for messages describing the cause exception and take the appropriate action. Also, examine the preceding or following log entriesthat are part of this message stack.

33

UPGAST-00001 to UPGAST-05024

UPGAST-00001
unable to continue due to an unexpected error

Category:
Upgrade

Cause:
An unexpected error occurred.

Action:
See the secondary error message for additional details.

UPGAST-00002
Invalid argument {0}; an argument must begin with a hyphen. Enter the command "{1} -help" for details.

Category:
Upgrade

Cause:
A command-line argument did not start with a hyphen.

Action:
Run the command again, using a hyphen to identify any arguments.

UPGAST-00003
invalid argument {0}. Enter the command "{0} -help" for details.

Category:
Upgrade

Cause:
The specified argument was not recognized.

Action:
Run the command again, specifying a valid argument.

UPGAST-00004
Value for argument {0} not supplied. Enter the command "{1} -help" for details.

Category:
Upgrade

Cause:
The value for a command-line argument was not specified.

Action:
Run the command again, specifying the required value for the command-line argument.

UPGAST-00007
Domain {0} is configured as a compact domain which is not a valid starting point for upgrade.

Category:
Upgrade

Cause:
A compact configured domain was specified.

Action:
Specify a domain that is not configured as a compact domain.

UPGAST-00008
failed to copy {0} to domain

Category:
Upgrade

Cause:
Unable to copy the specified file to the domain.

Action:
See the Upgrade Assistant log file for details.

UPGAST-00009
Invalid log level: {0}. Enter the command "{1} -help" for details.

Category:
Upgrade

Cause:
The log level specified was not recognized.

Action:
Run the command again, specifying a valid log level.

UPGAST-00010
Port number {0} is not valid.

Category:
Upgrade

Cause:
The port number specified was not a positive numeric value or was out of range.

Action:
Specify a valid port number.

UPGAST-00011
Host name {0} is not valid or unknown.

Category:
Upgrade

Cause:
Lookup of the specified host name failed.

Action:
Specify a valid host name.

UPGAST-00012
Required port is missing.

Category:
Upgrade

Cause:
A required port was not entered.

Action:
Enter the required port.

UPGAST-00013
Required user name is missing.

Category:
Upgrade

Cause:
A required user name was not entered.

Action:
Enter the required user name.

UPGAST-00014
unable to connect to WebLogic Server at {0}:{1}

Category:
Upgrade

Cause:
Failed connecting to the WebLogic Server at the specified host and port.

Action:
See the secondary error message for additional details.

UPGAST-00015
Required listen address is missing.

Category:
Upgrade

Cause:
A required listen address was not entered.

Action:
Enter the required listen address.

UPGAST-00016
Required password is missing.

Category:
Upgrade

Cause:
A required password was not entered.

Action:
Enter the required password.

UPGAST-00017
Required confirm password is missing.

Category:
Upgrade

Cause:
A required confirm password was not entered.

Action:
Enter the required confirm password.

UPGAST-00018
Password and confirm password do not match.

Category:
Upgrade

Cause:
The password and confirm password do not have the same value.

Action:
Enter the same value for the password and confirm password.

UPGAST-00019
User name may not contain commas, tabs, spaces, or any of the following characters: {0}

Category:
Upgrade

Cause:
An invalid user name was specified.

Action:
Enter the user name using only valid characters.

UPGAST-00020
Listen address {0} is not valid or unknown.

Category:
Upgrade

Cause:
Lookup of the specified listen address failed.

Action:
Specify a valid listen address.

UPGAST-00021
WLST script failure, see {0} for details

Category:
Upgrade

Cause:
The execution of a WLST script has failed

Action:
Check the specified WLST output file for the details of the failure.

UPGAST-00023
Standalone template {0} does not exist for component {1} of type {2}.

Category:
Upgrade

Cause:
A template was not found for the listed component.

Action:
Install the components standalone environment and then rerun the upgrade in that standalone environment.

UPGAST-00024
failed reading {0}

Category:
Upgrade

Cause:
Unable to read or parse the specified file.

Action:
See the secondary error message for additional details.

UPGAST-00025
The password must be at least 8 alphanumeric characters with at least one number or special character.

Category:
Upgrade

Cause:
An invalid password was specified.

Action:
Enter a password using 8 alphanumeric characters with at least one number or special character.

UPGAST-00026
failed reading {0}

Category:
Upgrade

Cause:
Unable to read or parse the specified OPMN file.

Action:
See the secondary error message for additional details.

UPGAST-00027
OPMN file {0} does not exist in the instance directory.

Category:
Upgrade

Cause:
The specified OPMN file did not exist.

Action:
Specify a valid instance directory where the specified OPMN file exists

UPGAST-00028
Template {0} does not exist for component {1} of type {2}.

Category:
Upgrade

Cause:
A template was not found for the listed component.

Action:
Install the listed component and then rerun the upgrade.

UPGAST-00029
Directory is not a valid domain for upgrade. {0}

Category:
Upgrade

Cause:
The specified directory was not a valid Oracle WebLogic domain for standalone upgrades. The domain was not created during a previous standalone upgrade.

Action:
Specify an Oracle WebLogic domain that is created during a previous standalone upgrade.

UPGAST-00030
The specified domain name {0} is invalid. It must include only alphanumeric characters, hyphens ("-") or underscore characters ("_") and contain at least one letter but must not start with a number.

Category:
Upgrade

Cause:
An invalid domain name was specified.

Action:
Enter a valid domain name.

UPGAST-00031
unable to get the active DomainMBean for the WebLogic Server domain

Category:
Upgrade

Cause:
Failed getting the active DomainMBean for the WebLogic Server domain.

Action:
Contact My Oracle Support.

UPGAST-00032
unable to communicate with the WebLogic Server

Category:
Upgrade

Cause:
Communication with the WebLogic Administrative Server was either lost or never established.

Action:
See the secondary error message for additional details.

UPGAST-00033
Required domain directory is missing.

Category:
Upgrade

Cause:
A required domain directory was not entered.

Action:
Enter the required domain directory.

UPGAST-00037
unable to fetch or store attribute "{0}" in the WebLogic Server

Category:
Upgrade

Cause:
The most common cause is an incorrect attribute name.

Action:
See the secondary error message for additional details.

UPGAST-00039
failed deleting {0}

Category:
Upgrade

Cause:
Unable to delete the specified file.

Action:
Manually delete the specified file.

UPGAST-00040
unable to get the DomainRuntimeMBean for the WebLogic Server domain

Category:
Upgrade

Cause:
Failed getting the DomainRuntimeMBean for the current WebLogic Server domain.

Action:
Contact My Oracle Support.

UPGAST-00041
unable to connect to WebLogic Server at {0}:{1}

Category:
Upgrade

Cause:
Failed connecting to the WebLogic Server at the specified host and port.

Action:
See the Upgrade Assistant log file for details.

UPGAST-00047
failed to read the installer inventory

Category:
Upgrade

Cause:
The install inventory could not be accessed.

Action:
See the secondary error message for additional details.

UPGAST-00048
unable to open the file

Category:
Upgrade

Cause:
Failed to open the file.

Action:
See the secondary error message for additional details.

UPGAST-00049
unable to read the file

Category:
Upgrade

Cause:
Failed to read the file.

Action:
See the secondary error message for additional details.

UPGAST-00050
unable to create logging directory: {0}

Category:
Upgrade

Cause:
The directory for log files could not be created.

Action:
See the secondary error message for additional details.

UPGAST-00051
unable to create the log file

Category:
Upgrade

Cause:
Failed to create the log file.

Action:
See the secondary error message for additional details.

UPGAST-00052
unable to initialize logging

Category:
Upgrade

Cause:
Initialization of logging failed.

Action:
See the secondary error message for additional details.

UPGAST-00053
No upgrade components were found in the config file {0}.

Category:
Upgrade

Cause:
No upgrade components in the specified configuration file.

Action:
Contact My Oracle Support.

UPGAST-00054
An error occurred loading the domain configuration file {0}

Category:
Upgrade

Cause:
Either the specified directory does not contain the expected file, or the file does not conform to the expected syntax.

Action:
Specify a valid WebLogic domain root directory.

UPGAST-00055
An error occurred loading the schema creation configuration file {0}

Category:
Upgrade

Cause:
An unexpected error occurred loading the schema creation configuration file.

Action:
Contact My Oracle Support. See the secondary error message for additional details.

UPGAST-00056
error initializing upgrade plug-in for {0}

Category:
Upgrade

Cause:
An unexpected error occurred initializing an upgrade plug-in.

Action:
Contact My Oracle Support. See the secondary error message for additional details.

UPGAST-00058
{0} file does not exist or cannot be accessed.

Category:
Upgrade

Cause:
The specified file did not exist or could not be accessed.

Action:
Make sure the path to the file is correct.

UPGAST-00079
failed to create temporary directory: {0}

Category:
Upgrade

Cause:
An error was encountered creating a temporary directory.

Action:
Ensure that the directory location exists and is not protected.

UPGAST-00093
{0} directory does not exist or is not a directory.

Category:
Upgrade

Cause:
The specified directory did not exist or was not a directory.

Action:
Specify a valid directory.

UPGAST-00094
{0} directory already exists.

Category:
Upgrade

Cause:
The specified directory already existed.

Action:
Specify a valid directory that does not exist.

UPGAST-00095
{0} directory is not writable.

Category:
Upgrade

Cause:
The specified directory must have write permissions.

Action:
Specify a directory that is writable or correct the permissions.

UPGAST-00096
error initializing the help system

Category:
Upgrade

Cause:
An error occurred while setting up the help system.

Action:
Contact My Oracle Support.

UPGAST-00097
The IP address of the host {0} cannot be determined.

Category:
Upgrade

Cause:
The network address of the specified host could not be determined.

Action:
Check the validity of the specified host.

UPGAST-00098
error setting the Oracle look-and-feel for the graphical user interface

Category:
Upgrade

Cause:
An error occurred while setting the appearance for the graphical user interface.

Action:
Contact My Oracle Support.

UPGAST-00107
The DISPLAY environment variable is not set. The graphical user interface (GUI) requires that this environment variable be set on UNIX.

Category:
Upgrade

Cause:
The required DISPLAY environment variable was not defined.

Action:
Set the required DISPLAY environment variable and then rerun the Upgrade Assistant.

UPGAST-00173
The plugin for {0} has requested an input value named {1} but that name is not in the upgrade descriptor.

Category:
Upgrade

Cause:
There was an inconsistency between the plugin descriptor definition and the input values requested by the plugin.

Action:
Contact My Oracle Support.

UPGAST-00174
failed to create or write to response file

Category:
Upgrade

Cause:
The file specified for saving responses could not be created or written to.

Action:
Specify a file in a location that is writable.

UPGAST-00175
Can not read response file {0}.

Category:
Upgrade

Cause:
The file specified for reading responses does not exist, or can not be read.

Action:
Specify a readable response file.

UPGAST-00176
Response file specifies an unknown upgrade step {0}.

Category:
Upgrade

Cause:
The response file specifies an upgrade that is unknown in this Fusion Middleware installation. Either the response file is for some other environment, or the Upgrade Descriptor files have not been properly installed.

Action:
Specify a response file generated for this installation.

UPGAST-00177
Response file line is not understood: {0}

Category:
Upgrade

Cause:
The response file contains syntax errors.

Action:
Correct the syntax errors in the response file and run the Upgrade Assistant again.

UPGAST-00178
Response file specifies a bad input name, {0}.

Category:
Upgrade

Cause:
The response file contains syntax errors, or is not of the correct version.

Action:
Correct the syntax errors in the response file and run the Upgrade Assistant again.

UPGAST-00180
error loading upgrade plug-in for {0}

Category:
Upgrade

Cause:
An unexpected error occurred loading an upgrade plug-in.

Action:
Contact My Oracle Support. See the secondary error message for additional details.

UPGAST-00181
error during execution of upgrade plug-in for {0}

Category:
Upgrade

Cause:
An unexpected error occurred during execution of an upgrade plug-in.

Action:
See the secondary error message for additional details.

UPGAST-00182
The examination phase for plug-in {0} will not be run due to a previous error.

Category:
Upgrade

Cause:
An error occurred when loading or initializing the plug-in which prevented the examination phase from running.

Action:
Review the log file for additional details.

UPGAST-00183
The upgrade phase for plug-in {0} will not be run due to a previous error.

Category:
Upgrade

Cause:
An error occurred when loading or initializing the plug-in which prevented the upgrade phase from running.

Action:
Review the log file for additional details.

UPGAST-00185
failed to load JDBC driver

Category:
Upgrade

Cause:
There was a failure loading a JDBC driver.

Action:
See the log file for details. Contact My Oracle Support.

UPGAST-00186
unable to connect to database as the DBA user name {0}

Category:
Upgrade

Cause:
Required fields to connect to a database were not supplied.

Action:
Enter the missing required fields and rerun.

UPGAST-00187
Unable to connect to WebLogic Admin Server. Some fields are empty.

Category:
Upgrade

Cause:
Required fields to connect to a WebLogic Admin Server were not supplied.

Action:
Enter the missing required fields and rerun.

UPGAST-00189
Exception raised while running an external command.

Category:
Upgrade

Cause:
An exception was raised while running an external command (such as sqlplus) in a subprocess. Check the stack trace for detailed information.

Action:
Attempt to correct the environment problem if any, then retry the upgrade. Contact My Oracle Support.

UPGAST-00190
{0} component version is {1}, status is {2}, upgraded flag is {3}

Category:
Upgrade

Cause:
After a successful schema upgrade the SCHEMA_VERSION_REGISTRY status column is not "VALID", or the upgraded column is not "Y".

Action:
Contact My Oracle Support.

UPGAST-00191
unable to validate the SCHEMA_VERSION_REGISTRY for component {0}

Category:
Upgrade

Cause:
An unexpected error occurred validating the SCHEMA_VERSION_REGISTRY.

Action:
Contact My Oracle Support.

UPGAST-00192
A dependency by component {0} on component {1} is unresolved.

Category:
Upgrade

Cause:
A required component was not found while discovering upgrade components and their dependencies.

Action:
Make sure the required component has been installed and that its upgrade descriptor XML file is in the plugins/upgrade directory of their product home.

UPGAST-00193
unable to connect to database for creating schemas {0}

Category:
Upgrade

Cause:
Required fields to connect to a database were not supplied.

Action:
Specify the missing required fields and rerun.

UPGAST-00194
An invalid component id for creating schemas was specified: {0}.

Category:
Upgrade

Cause:
An invalid component id was specified in the response file.

Action:
Specify a valid component for creating schemas.

UPGAST-00195
Edition name {0} specified in response file does not exist in database.

Category:
Upgrade

Cause:
The response file specified an edition name for creating schemas that does not exist.

Action:
Specify an existing edition name and rerun.

UPGAST-00196
The validate method for plug-in {0} will not be called due to a previous error.

Category:
Upgrade

Cause:
An error occurred when loading or initializing the plug-in which prevents the validate method from executing.

Action:
Review the log file for additional details.

UPGAST-00198
Descriptor tag {0} is only allowed in components of type={1}

Category:
Upgrade

Cause:
An upgrade plugin descriptor is improperly formed.

Action:
Contact My Oracle Support.

UPGAST-00200
Message reference {0} is not defined in resource bundle {1}.

Category:
Upgrade

Cause:
An upgrade plugin descriptor is referencing an undefined message.

Action:
Contact My Oracle Support.

UPGAST-00202
Unable to validate credentials. Some fields are empty.

Category:
Upgrade

Cause:
Required fields to validate credentials were not supplied.

Action:
Enter the missing required fields and rerun.

UPGAST-00203
validate method is not implemented by plug-in {0} for input named {1}.

Category:
Upgrade

Cause:
Required validate method was not implemented by plug-in or the signature of the validate method is incorrect.

Action:
Implement the required validate method with the correct signature.

UPGAST-00204
Response file specifies an unknown field "{0}".

Category:
Upgrade

Cause:
The response file specifies an input value with a qualified field name that is unknown for inputs of this type.

Action:
Specify a response file generated for this installation or correct your editing error.

UPGAST-00205
Response file specifies an incorrect or no format version. Version must be {0}.

Category:
Upgrade

Cause:
The fileFormatVersion specified in the [GENERAL] section of the file is either missing or incorrect for this program.

Action:
Generate new response files using the same version of the program that is going to read them.

UPGAST-00206
No upgrade descriptor files were found in the Oracle home, yet a response file was specified.

Category:
Upgrade

Cause:
Either this Oracle home contains no upgradable components and you are using a response file generated for a different installation, or the installation is incomplete or damaged.

Action:
Make sure that this installation is the one you intended to upgrade, and that the Upgrade Descriptor files are in the plugins/upgrade/ directories

UPGAST-00207
The Upgrade Descriptor in file {0} specifies a bad value "{1}" for the attribute named "{2}".

Category:
Upgrade

Cause:
An attribute in a tag in an Upgrade Descriptor, which provides information to the Upgrade Assistant about individual upgrade plugins, contains an improper value.

Action:
Contact My Oracle Support.

UPGAST-00208
An unrecognized database type "{0}" was specified in a descriptor or response file.

Category:
Upgrade

Cause:
Database type names in descriptor and response files must come from a fixed list of names. A name was encountered which is not on the list.

Action:
Correct the spelling of your database type and run the program again.

UPGAST-00209
directory path is not specified

Category:
Upgrade

Cause:
A required directory path was not entered.

Action:
Enter the required directory path.

UPGAST-00210
file path is not specified

Category:
Upgrade

Cause:
A required file path was not entered.

Action:
Enter the required file path.

UPGAST-00211
The response file specified a dependency on a plugin numbered {0} but either no plugin in the file has that as an INSTANCE value, or the descriptor file does not indicate that such a dependency is possible.

Category:
Upgrade

Cause:
All dependsOnPluginInstance properties must refer to numbers defined earlier in the response file with a pluginInstance property, and must refer to a plugin to which such a dependency is allowed by the upgrade descriptor file.

Action:
If you created or edited the response file, correct the error and try again. If this is a response file generated by the Upgrade Assistant, contact My Oracle Support.

UPGAST-00212
unable to connect to database as the schema user {0}

Category:
Upgrade

Cause:
Required fields to connect to a database were not supplied.

Action:
Enter the missing required fields and rerun.

UPGAST-00213
Unable to connect to database as the dba user "{0}".

Category:
Upgrade

Cause:
The database connection failed for the specified reason.

Action:
See the secondary error message for additional details.

UPGAST-00214
Unable to connect to database as the schema user "{0}".

Category:
Upgrade

Cause:
The database connection failed for the specified reason.

Action:
See the secondary error message for additional details.

UPGAST-00215
Upgrade is not being done due to examine failures.

Category:
Upgrade

Cause:
When using a response file, actual upgrades are not done if any plugin can not complete its EXAMINE phase.

Action:
Correct the problem using information provided in the log file; then retry the operation.

UPGAST-00216
A library file "{0}" referred to in an Upgrade Descriptor file does not exist.

Category:
Upgrade

Cause:
Upgrade Plugins can refer to other JAR files. A file in such a reference can not be found. This can be caused by an incorrect installation.

Action:
Contact My Oracle Support

UPGAST-00217
directory path is not specified {0}

Category:
Upgrade

Cause:
A required directory path was not entered.

Action:
Enter the required directory path.

UPGAST-00218
file path is not specified {0}

Category:
Upgrade

Cause:
A required file path was not entered.

Action:
Enter the required file path.

UPGAST-00219
No schemas were found for component {0} in the Schema Version Registry.

Category:
Upgrade

Cause:
A database query to get a list of schemas from the Schema Version Registry returned an empty list.

Action:
Verify that you have schemas for the specified component.

UPGAST-00220
failed to get a list of schemas from the Schema Version Registry

Category:
Upgrade

Cause:
A database query to get a list of schemas from the Schema Version failed.

Action:
See the secondary error message for additional details.

UPGAST-00221
unexpected error upgrading schema

Category:
Upgrade

Cause:
An unexpected error occurred during schema upgrade.

Action:
Check the error messages in the Upgrade Assistant log files. Correct the problem before running the Upgrade Assistant again.

UPGAST-00222
invalid database type specified

Category:
Upgrade

Cause:
An invalid database type was specified.

Action:
The database type specified is not supported by the RCU JDBCEngine. Contact My Oracle Support.

UPGAST-00223
The upgrade of "{0}" is being skipped because the upgrade for "{1}" has either failed or been skipped.

Category:
Upgrade

Cause:
One component upgrade which is a pre-requisite for a second component's upgrade has not finished successfully. Therefore the second component's upgrade has not been executed.

Action:
Fix the original problem and run Upgrade again.

UPGAST-00224
The specified database does not contain any schemas for {0} or the database user lacks privilege to view the schemas.

Category:
Upgrade

Cause:
The database you have specified does not contain any schemas registered as belonging to the component you are upgrading, or else the current database user lacks privilege to query the contents of the schema version registry.

Action:
Verify that the database contains schema entries in schema version registry. If it does not, specify a different database. Verify that the user has DBA privilege. Connect to the database as DBA.

UPGAST-00225
The response file contains a non-numeric value "{0}" where a number is required.

Category:
Upgrade

Cause:
Plugin ID numbers must be decimal integers.

Action:
Correct the response file and run the program again.

UPGAST-00226
The database connect string format is incorrect. The correct format is: {0}

Category:
Upgrade

Cause:
The database connect string format was specified incorrectly.

Action:
Enter the database connect string using the correct format.

UPGAST-00227
Oracle instance directory path is not specified

Category:
Upgrade

Cause:
A required Oracle instance directory path was not entered.

Action:
Enter the required Oracle instance directory path.

UPGAST-00228
Oracle instance directory path is not specified {0}

Category:
Upgrade

Cause:
A required Oracle instance directory path was not entered.

Action:
Enter the required Oracle instance directory path.

UPGAST-00229
The directory {0} is not an 11g Oracle instance directory.

Category:
Upgrade

Cause:
The directory specified was not a valid 11g Oracle instance directory.

Action:
Enter a valid 11g Oracle instance directory.

UPGAST-00230
No editions were found

Category:
Upgrade

Cause:
A database query to get a list of editions returned an empty list.

Action:
Verify that you have editions enabled and have created one or more editions.

UPGAST-00231
failed to get a list of editions

Category:
Upgrade

Cause:
A database query to get a list of editions failed

Action:
See the secondary error message for additional details.

UPGAST-00232
database query for compatibility failed: {0}

Category:
Upgrade

Cause:
A database query to check that database compatibility is 11.2.0 or greater failed

Action:
See the secondary error message for additional details.

UPGAST-00233
database compatibility must be 11.2.0 or greater not {0}

Category:
Upgrade

Cause:
An EBR-enabled Oracle database requires that compatibility parameter be set to "11.2.0" or greater. However the actual compatibility was less than version 11.2.0

Action:
Issue the SQL command ALTER SYSTEM SET COMPATIBLE = '11.2.0' SCOPE=SPFILE.

UPGAST-00234
Unable to connect to database using SSL settings as the dba user "{0}".

Category:
Upgrade

Cause:
The database connection failed for the specified reason. The connection failure could be due to incorrect SSL settings or incorrect database setup.

Action:
See the secondary error message(s) and the Upgrade Assistant log file for additional details.

UPGAST-00235
Schema version registry table does not exist for component {0}

Category:
Upgrade

Cause:
An attempt to list the contents of the schema version registry table for the component failed because the schema version registry does not exist.

Action:
This is an informational message. No further action is necessary.

UPGAST-00236
There is no schema version registry entry for component {0}

Category:
Upgrade

Cause:
An attempt to list the contents of the schema version registry table for the component failed because no registry entry exists for the component.

Action:
This is an informational message. No further action is necessary.

UPGAST-00237
A duplicate component definition for component {0} has been detected in product home {1}.

Category:
Upgrade

Cause:
Component names must be unique within an Oracle home. Either the component descriptor files are incorrect, or multiple copies of the same component have been installed in the same Oracle home.

Action:
Remove the duplicate installations, or contact My Oracle Support.

UPGAST-00238
Warning: A dependency by component {0} on component {1} is unresolved. Upgrades of component {0} will be disabled.

Category:
Upgrade

Cause:
A dependent component was not found while discovering upgrade components and their dependencies.

Action:
Make sure the required component has been installed.

UPGAST-00239
messageclass attribute must be specified for message reference {0}

Category:
Upgrade

Cause:
A resource bundle was not specified in the component's upgrade descriptor.

Action:
Specify the component's resource bundle using the messageclass attribute.

UPGAST-00240
An unexpected error was encountered while monitoring the progress of a plugin.

Category:
Upgrade

Cause:
During the upgrade phase of a plugin, the upgrade monitor thread encountered an error while shutting down

Action:
The Fusion Middleware schema upgrade was not impacted and the error can be ignored.

UPGAST-00244
unable to connect to {0} Server {1}

Category:
Upgrade

Cause:
Required fields to connect to the specified Server were not supplied.

Action:
Enter the missing required fields and rerun.

UPGAST-00245
An unexpected error has occurred while initializing internal data structures.

Category:
Upgrade

Cause:
A problem was encountered while setting up the internal WLS descriptor.

Action:
Contact My Oracle Support

UPGAST-00246
The selected domain has a version of {0} which is less than the minimum of {1}.

Category:
Upgrade

Cause:
Upgrade requires the domain to be at a certain minimum version, which this domain does not meet.

Action:
Select a different domain, or run the Reconfiguration tool before trying to upgrade.

UPGAST-00247
unable to connect to WebLogic Server at {0}:{1} {2}

Category:
Upgrade

Cause:
Failed connecting to the WebLogic Server at the specified host and port.

Action:
See the secondary error message for additional details.

UPGAST-00248
Descriptor item {0} missing required "text" attribute.

Category:
Upgrade

Cause:
The named input tag in an upgrade descriptor does not have a required "text" attribute.

Action:
Contact My Oracle Support.

UPGAST-00249
isOptionalInputRequired method is not implemented by plug-in {0} for input named {1}.

Category:
Upgrade

Cause:
Required isOptionalInputRequired method was not implemented by plug-in or the signature of the isOptionalInputRequired is incorrect.

Action:
Implement the required isOptionalInputRequired method with the correct signature.

UPGAST-00250
Required input {0} is missing from section {1} in the response file.

Category:
Upgrade

Cause:
The response file does not supply any values for a required input.

Action:
Correct the response file and retry the upgrade.

UPGAST-00251
An error occurred reading Upgrade Descriptor file {0}

Category:
Upgrade

Cause:
The file does not conform to the expected syntax.

Action:
See the secondary message for additional information. Contact My Oracle Support.

UPGAST-00252
Required input {0} is missing from section {1} in response file.

Category:
Upgrade

Cause:
The response file does not supply any values for an optional input that the plugin indicates it needs in this case.

Action:
Correct the response file and retry the upgrade.

UPGAST-00254
invalid response file contents

Category:
Upgrade

Cause:
The response file is not a valid response file.

Action:
Specify a response file generated for this installation or correct your editing error. See secondary message for details.

UPGAST-00255
More than one component definition contains an upgrade for a component. The following component descriptor files each contain an upgrade for component {0}: {1}

Category:
Upgrade

Cause:
There must be only one upgrader of a component within an Oracle home. Two or more schema input declarations exist that are upgrading the same component-id.

Action:
Remove the duplicate upgrades, or contact My Oracle Support.

UPGAST-00256
Upgrade is being skipped because the -examine flag is set

Category:
Upgrade

Cause:
When using a response file, actual upgrades are not done when the -examine command line option is set.

Action:
If you want to perform an actual upgrade in response file mode remove the -examine flag from the command line. If you intended to perform just the examine phase, no action is necessary.

UPGAST-00257
The -examine flag is only allowed with the -response flag

Category:
Upgrade

Cause:
You cannot specify -examine command line option without the -response option.

Action:
You cannot specify the -examine flag when running the upgrade tool in GUI mode. If you want to perform an examine without an actual upgrade you must also specify -response on the command line.

UPGAST-00258
Component plugin {0} named in response file is not in domain {1}.

Category:
Upgrade

Cause:
The response file references a component plugin which is not configured in the specified domain.

Action:
Specify a response file generated for this domain.

UPGAST-00259
The getInitialValue method for plug-in {0} will not be called due to a previous error.

Category:
Upgrade

Cause:
An error occurred when loading or initializing the plug-in which prevents the getInitialValue method from executing.

Action:
Review the log file for additional details.

UPGAST-00260
getInitialValue method is not implemented by plug-in {0} for input named {1}.

Category:
Upgrade

Cause:
Required getInitialValue method was not implemented by plug-in or the signature of the getInitialValue method is incorrect.

Action:
Implement the required getInitialValue method with the correct signature.

UPGAST-00261
The isOptionalInputRequired method for plug-in {0} will not be called due to a previous error.

Category:
Upgrade

Cause:
An error occurred when loading or initializing the plug-in which prevents the isOptionalInputRequired method from executing.

Action:
Review the log file for additional details.

UPGAST-00262
The log directory did not exist or cannot be accessed: {0}.

Category:
Upgrade

Cause:
The log directory specified was not recognized as an existing, writable directory.

Action:
Run the command again, specifying a valid log directory. If necessary create the log directory and make sure it is a writable directory. See the command line help for details.

UPGAST-00263
The response file contained both configuration type and schema type upgrades.

Category:
Upgrade

Cause:
The response file contains a mix of configuration type and schema type upgrades.

Action:
Change the response file to specify only configuration type or schema type upgrades then rerun the upgrade.

UPGAST-00264
Bad "name" attribute value in Upgrade Descriptor.

Category:
Upgrade

Cause:
Names in Upgrade Descriptor files must be alphanumeric.

Action:
Correct the name.

UPGAST-00265
Directory is not a valid domain for upgrade. {0}

Category:
Upgrade

Cause:
The specified directory was not a valid Oracle WebLogic domain.

Action:
Specify an existing WebLogic domain directory.

UPGAST-00266
Oracle instance directory {0} is not a unique directory path.

Category:
Upgrade

Cause:
A duplicate Oracle instance directory path was specified.

Action:
Specify Oracle instance directoies that are not duplicated.

UPGAST-00267
isUpgradeRequired method is not implemented by plug-in {0}.

Category:
Upgrade

Cause:
Required isUpgradeRequired method was not implemented by plug-in or the signature of the isUpgradeRequired is incorrect.

Action:
Implement the required isUpgradeRequired method with the correct signature.

UPGAST-00268
The response file specified is not for a standalone upgrade.

Category:
Upgrade

Cause:
The response file contained WebLogic credentials that are not valid during a standalone upgrade.

Action:
Regenerate the response file and rerun the upgrade.

UPGAST-00269
The response file specified is not for an upgrade requiring WebLogic credentials.

Category:
Upgrade

Cause:
The response file does not contain WebLogic credentials that are required during an online upgrade.

Action:
Regenerate the response file and rerun the upgrade.

UPGAST-00270
Directory is not a valid domain for upgrade. {0}

Category:
Upgrade

Cause:
The specified directory was not a valid Oracle WebLogic domain.

Action:
See the log file for details. Specify a valid WebLogic domain directory.

UPGAST-00271
Validation of specified domain failed. {0}

Category:
Upgrade

Cause:
The specified domain failed validation which will prevent domain reconfiguration.

Action:
Refer to the Troubleshooting section of your upgrade documentation for info on supported domain upgrades. See the log file for details of the validation failure.

UPGAST-00272
Unable to connect to EBR-enabled Oracle database for schema {0} because an edition name was not specified.

Category:
Upgrade

Cause:
An edition name must be provided to establish a connection to an EBR-enabled Oracle Database.

Action:
Add an edition name to the response file (when using response file mode).

UPGAST-00273
Initialization of the inputs for schema {0} in component {1} failed with the error: {2}

Category:
Upgrade

Cause:
One of the inputs was not valid.

Action:
See the secondary error message for additional details.

UPGAST-00280
The -examine flag is not allowed with the -readiness flag

Category:
Upgrade

Cause:
You cannot specify -examine command line option with the -readiness option.

Action:
You cannot specify the -examine flag when running the upgrade tool in readiness check mode. If you want to perform an examine without an actual upgrade you must remove the -response option from the command line.

UPGAST-00281
Upgrade is being skipped because the -readiness flag is set

Category:
Upgrade

Cause:
Actual upgrades are not done when the -readiness command line option is set.

Action:
If you want to perform an actual upgrade remove the -readiness flag from the command line. If you intended to perform just the readiness phase, no action is necessary.

UPGAST-00282
Upgrade readiness check completed with one or more errors.

Category:
Upgrade

Cause:
Examine the readiness check report file and the log file to understand which checks failed.

Action:
Correct the problem using information provided in the log file; then retry the operation.

UPGAST-00283
The readiness check phase for plug-in {0} will not be run due to a previous error.

Category:
Upgrade

Cause:
An error occurred when loading or initializing the plug-in which prevents the readiness check phase from running.

Action:
Review the log file for additional details.

UPGAST-00284
The isUpgradeRequired method for plug-in {0} will not be called due to a previous error.

Category:
Upgrade

Cause:
An error occurred when loading or initializing the plug-in which prevents the isUpgradeRequired method from executing.

Action:
Review the log file for additional details.

UPGAST-00286
A response file referenced one or more schema user names that did not have a matching datasource in the specified domain.

Category:
Upgrade

Cause:
The auto-datasource option found one or more schema user names that did not have a matching datasource.

Action:
Review the domain's datasources and response file specified during upgrade to identify the mismatch.

UPGAST-00287
The getPluginInstantiationCount method for plug-in {0} will not be called due to a previous error.

Category:
Upgrade

Cause:
An error occurred when loading or initializing the plug-in which prevents the getPluginInstantiationCount method from executing.

Action:
Review the log file for additional details.

UPGAST-00288
Duplicate schema version registry entries matched the auto-datasource query.

Category:
Upgrade

Cause:
The auto-datasource option found more than one schema version registry entry that matched the component-id and data source user name.

Action:
Contact My Oracle Support.

UPGAST-00289
Plugin {0} disabled, isUpgradeRequired returned exception.

Category:
Upgrade

Cause:
The plugin threw an exception while processing the request to determine if it has schemas within the domain to upgrade.

Action:
Contact My Oracle Support.

UPGAST-00290
Plugin {0} disabled, the auto-datasource request returned an error.

Category:
Upgrade

Cause:
The auto-datasource option failed while processing the request for this plugin.

Action:
Contact My Oracle Support.

UPGAST-00291
The schema newversion attribute is missing for component {0}

Category:
Upgrade

Cause:
The upgrade framework has detected that the required schema newversion= attribute was missing in an upgrade descriptor file.

Action:
Correct the upgrade descriptor file. Starting in release 12.1.3 the <schema> tags must include a newversion= attribute that shows what the schema version number will become after sucecssful upgrade.

UPGAST-00292
Null value found in UAWLSINTERNAL field "{0}" of the response file.

Category:
Upgrade

Cause:
A value necessary for identifying the WLS domain is missing.

Action:
Correct the response file and rerun the upgrade.

UPGAST-00294
Unable to establish a connection to a WLS server.

Category:
Upgrade

Cause:
Attempt was made to connect to a WLS server during an offline upgrade.

Action:
Correct the response file and rerun the upgrade.

UPGAST-00296
The Upgrade Descriptor in file {0} specifies an illegal combination of attributes "{1}" and "{2}".

Category:
Upgrade

Cause:
A tag in an Upgrade Descriptor, which provides information to the Upgrade Assistant about individual upgrade plugins, contains two attributes whose values are incompatible with each other.

Action:
Contact My Oracle Support.

UPGAST-00297
no text found for offset {0}, read amount {1}, document length {2}

Category:
Upgrade

Cause:
Unknown; possibly the result of previous errors.

Action:
Refresh the file viewer window if possible.

UPGAST-00298
find position {0}, offset, {1}, search string {2}

Category:
Upgrade

Cause:
Unknown; possibly the result of previous errors.

Action:
Refresh the file viewer window if possible.

UPGAST-00300
The preselected check box for {0} has been deselected by the user

Category:
Upgrade

Cause:
The user has manually unchecked an upgrade item that was preselected by Upgrade Assistant.

Action:
Make sure that Oracle's recommendation to always upgrade this item really does not apply to your situation. If you are unsure then this box should be checked in most cases

UPGAST-00301
getTableRowCount method is not implemented by plug-in {0} for input named {1}.

Category:
Upgrade

Cause:
Required getTableRowCount method was not implemented by plug-in or the signature of the getTableRowCount method is incorrect.

Action:
Implement the required getTableRowCount method with the correct signature.

UPGAST-00302
An exception occurred while constructing the backing model for table input {0}.

Category:
Upgrade

Cause:
A call to the plugin method "getTableRowCount" or "getInitialValue" failed.

Action:
See the log file for exception details.

UPGAST-00303
Schema upgrade disabled for plugin {0} because feature set {1} is not installed.

Category:
Upgrade

Cause:
A plugin declared a dependency on a feature set, and the needed feature set is not installed. Schema upgrade of the component is disallowed.

Action:
No action is necessary.

UPGAST-00304
The updateOptionalInputPage method cannot be called for the non-optional input {0}.

Category:
Upgrade

Cause:
An error occurred calling the updateOptionalInputPage method.

Action:
Change the specified input to be optional.

UPGAST-00305
The updateOptionalCustomInput method cannot be called for the non-optional input {0}.

Category:
Upgrade

Cause:
An error occurred calling the updateOptionalCustomInput method.

Action:
Change the specified input to be optional.

UPGAST-00306
The updateOptionalInputPage method can only be called for top level inputs. Input {0} is a custom input or option input.

Category:
Upgrade

Cause:
An error occurred calling the updateOptionalInputPage method.

Action:
Change the specified input to be a top level input.

UPGAST-00307
The updateOptionalCustomInput method cannot be called for the non-custom input {0}.

Category:
Upgrade

Cause:
An error occurred calling the updateOptionalCustomInput method.

Action:
Change the specified input to be a custom input.

UPGAST-00308
An exception occurred while resizing the backing model for table input {0}.

Category:
Upgrade

Cause:
A call to the plugin method "getTableRowCount" failed.

Action:
See the log file for exception details.

UPGAST-00309
An invalid database URL was specified for schema {0}: {1}

Category:
Upgrade

Cause:
An incorrectly formed database URL was identified.

Action:
Contact My Oracle Support.

UPGAST-00310
An invalid database URL was specified for datasource {0} with schema {1}: {2}

Category:
Upgrade

Cause:
An incorrectly formed database URL was identified for the specified datasource.

Action:
Fix the datasource definition in your domain configuration using the WebLogic Server Administration Console.

UPGAST-00311
configUpgrade is not allowed in combination with schemaUpgrade.

Category:
Upgrade

Cause:
You cannot use both schemaUpgrade and configUpgrade in the same command.

Action:
Use only schemaUpgrade if you intend to upgrade your FMW schemas; use only configUpgrade if you intend to upgrade your FMW configurations.

UPGAST-00312
readiness is not allowed with configUpgrade or schemaUpgrade.

Category:
Upgrade

Cause:
You cannot use readiness with either configUpgrade or schemaUpgrade.

Action:
When performing readiness do not specify either the -configUpgrade option or the -schemaUpgrade option. When performing an upgrade do not specify the -readiness option.

UPGAST-00313
The response file contains components that do not match the specified upgrade type.

Category:
Upgrade

Cause:
The response file does not contain inputs that match the type of upgrade specified.

Action:
Regenerate the response file if necessary and rerun the upgrade. Specify a response file with schema inputs when performing a schema upgrade.Specify a response file with configuration inputs when performing a configuration upgrade.

UPGAST-00314
The XML parser reported a problem.

Category:
Upgrade

Cause:
Something unexpected occurred while parsing an XML file.

Action:
No action is necessary unless XML processing was aborted and the Upgrade Assistant was unable to continue. In which case the XML file in question should be identified and corrected. See the log file for exception details.

UPGAST-00315
The Repository Creation Utility (RCU) API returned an unexpected result.

Category:
Upgrade

Cause:
The RCU API completed with an unexpected result.

Action:
See the log file for details. Contact My Oracle Support.

UPGAST-00320
Exception raised while running a concurrent upgrade task. {0}

Category:
Upgrade

Cause:
An exception was raised while running a upgrade task in a concurrent thread. Check the stack trace for detailed information.

Action:
Attempt to correct the environment problem if any, then retry the upgrade. Contact My Oracle Support.

UPGAST-00321
The -threads option was passed an illegal value for number of threads: {0}. Must be an integer from {1} to {2}.

Category:
Upgrade

Cause:
The -threads option was passed a value that is outside the permitted range of threads.

Action:
Run the command again, specifying a valid number of threads, this value determines the number of schema upgrade plugins that can be run at the same time. See the command line help for details.

UPGAST-00323
Was unable to terminate the thread executor pool

Category:
Upgrade

Cause:
The thread pool that is used to schedule multiple plugins concurrently, could not be terminated after being shut down. The cause of this is unknown.

Action:
There is a very long timeout in order to give the thread pool ample time to terminate but the timeout period was still exceeded. There should not be any adverse affect due to this error

UPGAST-00324
Was unable to terminate the thread executor pool, timeout reached while performing {0}.

Category:
Upgrade

Cause:
The thread pool that is used to schedule multiple plugins concurrently, could not be terminated after being shut down. The timeout period was reached

Action:
There is a very long timeout in order to give the thread pool ample time to terminate but the timeout period was still exceeded. There should not be any adverse affect due to this error.

UPGAST-00325
database query for server identify failed: {0}

Category:
Upgrade

Cause:
A database query to compare database server identity failed

Action:
See the secondary error message for additional details.

UPGAST-00328
The schema version registry table does not exist on this database.

Category:
Upgrade

Cause:
The schema version registry table does not exist, because the required 12c schemas, such as the new Service Table schema, have not been created by RCU. The registry table must exist in order to run Upgrade Assistant.

Action:
Create the required 12c schema using RCU before running the Upgrade Assistant. Refer to the upgrade planning guide for the list of required schemas for this release.

UPGAST-00330
Unable to query schema version registry for schema: {0}

Category:
Upgrade

Cause:
An attempt to perform schema version registry queries failed.

Action:
See the secondary error message for additional details.

UPGAST-00331
Option -output requires -backupRegistry

Category:
Upgrade

Cause:
Option -output is only valid with -backupRegistry.

Action:
Remove -output from the command line.

UPGAST-00352
The -readiness option is not allowed in a standalone environment.

Category:
Upgrade

Cause:
You cannot specify the -readiness option in a standalone installation.

Action:
No action is necessary.

UPGAST-00353
Upgrade readiness check was unable to locate a standard query method for {0}

Category:
Upgrade

Cause:
Readiness check was unable to locate the code for a standard query.

Action:
Contact My Oracle Support.

UPGAST-00355
The selected domain has a version of {0} which appears to not be a valid version number.

Category:
Upgrade

Cause:
Upgrade requires the domain to be at a certain version, which this domain does not meet.

Action:
Select a different domain, or run the Reconfiguration tool before trying to upgrade.

UPGAST-00356
The specified domain has a version of {0} which is less than the minimum of {1}.

Category:
Upgrade

Cause:
The domain is at a version less than the minimum version.

Action:
Specify a domain that is more recent than the minimum viable version.

UPGAST-00357
Upgrade readiness check returned an empty result set for test {0}, schema tag {1}, database object {2}

Category:
Upgrade

Cause:
Readiness check encountered an error during execution of a standard query.

Action:
Contact My Oracle Support.

UPGAST-00358
Upgrade readiness check encountered an unexpected error for test {0}, schema tag {1}, database object {2}

Category:
Upgrade

Cause:
Readiness check encountered an error during execution of a standard query.

Action:
Contact My Oracle Support.

UPGAST-00359
Upgrade readiness check encountered a method invocation error for test {0}, schema tag {1}, database object {2}, query {3}

Category:
Upgrade

Cause:
Readiness check encountered an error during execution of a standard query.

Action:
Contact My Oracle Support.

UPGAST-0370
getTablespaceName is only supported for Oracle Database not {0}.

Category:
Upgrade

Cause:
An upgrade plugin used an API that is only supported for the Oracle Database.

Action:
Contact My Oracle Support.

UPGAST-00371
A database query to return tablespace name failed: {0}

Category:
Upgrade

Cause:
A database query to identify the tablespace failed

Action:
See the secondary error message for additional details.

UPGAST-00372
A database query to detect consolidated schema failed: {0}

Category:
Upgrade

Cause:
A database query to detect if this schema is consolidated failed

Action:
See the secondary error message for additional details.

UPGAST-00373
A readiness check that does not apply to consolidated schemas has been skipped for test {0}, schema tag {1}, database object {2}

Category:
Upgrade

Cause:
A standard readiness test was called that does not apply to consolidated schemas. The upgrade framework has skipped the test. This is a successful outcome.

Action:
No further action is necessary.

UPGAST-00374
SQL Query failed because it is only applicable to a consolidated schema: {0}

Category:
Upgrade

Cause:
A database query that obtains information specific to consolidated schemas was called for a non-consolidated schema.

Action:
No further action is necessary.

UPGAST-05001
Error connecting to {0} as user {1}.

Category:
Upgrade

Cause:
A error occurred attempting to connect to the specified database.

Action:
See the secondary error message for additional details.

UPGAST-05002
Error creating Java DB schema {0}.

Category:
Upgrade

Cause:
A error occurred attempting to create the specified Java DB schema.

Action:
See the secondary error message for additional details.

UPGAST-05003
Error getting the Java DB Schema Version Registry table.

Category:
Upgrade

Cause:
A error occurred locating the Schema Version Registry table for a Java DB.

Action:
See the secondary error message for additional details.

UPGAST-05004
Error registering the JDBC drver class {0}.

Category:
Upgrade

Cause:
A error occurred registering the specified JDBC driver.

Action:
See the secondary error message for additional details.

UPGAST-05005
Unsupported database {0} identified.

Category:
Upgrade

Cause:
A database that is not supported was specified.

Action:
Specify a supported database.

UPGAST-05006
Error moving the Schema Version Registry table.

Category:
Upgrade

Cause:
A error occurred while moving the Schema Version Registry table from SYSTEM to FMWREGISTRY.

Action:
See the secondary error message for additional details.

UPGAST-05007
Error dropping the view SYSTEM.SCHEMA_VERSION_REGISTRY.

Category:
Upgrade

Cause:
A error occurred while dropping the database view SYSTEM.SCHEMA_VERSION_REGISTRY.

Action:
See the secondary error message for additional details.

UPGAST-05008
Error copying the contents of schema version registry table.

Category:
Upgrade

Cause:
A error occurred while copying the contents of table SYSTEM.SCHEMA_VERSION_REGISTRY$ to table FMWREGISTRY.SCHEMA_VERSION_REGISTRY$.

Action:
See the secondary error message for additional details.

UPGAST-05009
Error adding triggers to the schema version registry table.

Category:
Upgrade

Cause:
A error occurred while adding triggers to the table SYSTEM.SCHEMA_VERSION_REGISTRY$.

Action:
See the secondary error message for additional details.

UPGAST-05010
Error getting the metadata for the database connection.

Category:
Upgrade

Cause:
A error occurred while requesting the metadata for a database connection.

Action:
See the secondary error message for additional details.

UPGAST-05011
Error testing if the database environment allows creation of system objects.

Category:
Upgrade

Cause:
A error occurred while testing if the database connection allows the creation of system objects.

Action:
See the secondary error message for additional details.

UPGAST-05012
Error testing if the database table exists.

Category:
Upgrade

Cause:
A error occurred while testing if the table {0} exists.

Action:
See the secondary error message for additional details.

UPGAST-05013
Error creating a SYSTEM instance of the schema version registry table.

Category:
Upgrade

Cause:
A error occurred while creating a schema version registry table in SYSTEM for compatibility with pre-FMWREGISTRY code.

Action:
See the secondary error message for additional details.

UPGAST-05014
Error creating the database view SYSTEM.SCHEMA_VERSION_REGISTRY.

Category:
Upgrade

Cause:
A error occurred while creating a database view for for the schema version registry table.

Action:
See the secondary error message for additional details.

UPGAST-05015
Error granting access for SYSTEM instance of the schema version registry.

Category:
Upgrade

Cause:
A error occurred while creating access rights for the SYSTEM instance of the schema version registry to access the FMWREGISTRY instance.

Action:
See the secondary error message for additional details.

UPGAST-05016
Unrecognized database type of {0} was specified.

Category:
Upgrade

Cause:
A database type that is not recognized was specified.

Action:
Specify a supported database type.

UPGAST-05017
Error creating the public synonym SCHEMA_VERSION_REGISTRY.

Category:
Upgrade

Cause:
An error occurred while creating the database synonym SCHEMA_VERSION_REGISTRY.

Action:
See the secondary error message for additional details.

UPGAST-05018
Error dropping the public synonym SCHEMA_VERSION_REGISTRY.

Category:
Upgrade

Cause:
An error occurred while dropping the database synonym SCHEMA_VERSION_REGISTRY.

Action:
See the secondary error message for additional details.

UPGAST-05019
Error dropping the trigger SYSTEM.{0}.

Category:
Upgrade

Cause:
An error occurred while dropping the database trigger specified.

Action:
See the secondary error message for additional details.

UPGAST-05020
Error dropping the view {0}.SCHEMA_VERSION_REGISTRY.

Category:
Upgrade

Cause:
An error occurred while dropping the database view specified.

Action:
See the secondary error message for additional details.

UPGAST-05021
Error dropping the table {0}.SCHEMA_VERSION_REGISTRY$.

Category:
Upgrade

Cause:
An error occurred while dropping the database table specified.

Action:
See the secondary error message for additional details.

UPGAST-05022
Error dropping the user {0}.

Category:
Upgrade

Cause:
An error occurred while dropping the database user specified.

Action:
See the secondary error message for additional details.

UPGAST-05023
Unable to backup schema version registry: {0}

Category:
Upgrade

Cause:
An error occurred while attempting to backup the schema version registry

Action:
See the log file for exception details.

UPGAST-05024
Internal error restoring schema version registry: {0}/{1}

Category:
Upgrade

Cause:
Unexpected data detected while attempting to restore the schema version registry

Action:
Contact My Oracle Support.

34
UPG-OHS-00001 to UPG-OHS-00013

UPG-OHS-00001
Source path {0} does not refer to an Oracle HTTP Server {1} component.

Category:
UA

Cause:
An invalid source directory was specified.

Action:
Select a valid Oracle HTTP Server component configuration directory.

UPG-OHS-00002
An unknown error occurred while logging the migration results from file {0}.

Category:
UA

Cause:
The file specified could not be read, or Upgrade Assistant logging failed.

Action:
Check for other errors with the upgrade task.

UPG-OHS-00003
The configuration file {0} has an invalid format.

Category:
UA

Cause:
The file specified cannot be parsed due to an invalid or unexpected format.

Action:
The information in the file specified must be migrated manually.

UPG-OHS-00004
An error occurred while updating configuration file {0}.

Category:
UA

Cause:
The cause is unknown.

Action:
The information in the file specified must be migrated manually.

UPG-OHS-00005
An error occurred while copying configuration file {0} to {1}.

Category:
UA

Cause:
The cause is unknown.

Action:
The source file specified must be manually copied to the destination file specified.

UPG-OHS-00006
An error occurred while reading file {0}.

Category:
UA

Cause:
The cause is unknown.

Action:
The information in the file specified must be migrated manually.

UPG-OHS-00007
The OHS version {0} is not supported for upgrade.

Category:
UA

Cause:
This OHS Upgrade Assistant plugin supports upgrade only from OHS 11.1.1.6.0 onwards.

Action:
Upgrade to a minimum supported version(11.1.1.6.0) and then try to upgrade henceforth.

UPG-OHS-00008
The files at location {0} are inaccessible.

Category:
UA

Cause:
Files at this location do not have required permissions.

Action:
Change the access permissions of the files at this location.

UPG-OHS-00009
Path {0} does not exist.

Category:
UA

Cause:
The expected file is missing.

Action:
Verify the source OHS installation.

UPG-OHS-00010
Unable to parse {0} of the domain.

Category:
UA

Cause:
The syntax of the file is incorrect.

Action:
Verify that the configuration of source domain is proper.

UPG-OHS-00011
The import of wallet failed.

Category:
UA

Cause:
KSS operations failed.

Action:
Import the wallets manually.

UPG-OHS-00012
KSS operations failed.

Category:
UA

Cause:
The cause is unknown.

Action:
Import the wallets manually.

UPG-OHS-00013
An MD5 or MD2 certificate with subject {0}, issuer {1}, and algorithm {2} is present at the location {3}.

Category:
UA

Cause:
Presence of insecure certificate.

Action:
Replace the certificate manually.

35

WC-05319 to WC-05370

WC-05319
Failed to retrieve security parent portal for the child portal {0}

Category:
Other

Cause:
Failure in retrieving security parent

Action:
Contact Administrator.

WC-05320
Failed to copy security data for portal {0}

Category:
Other

Cause:
Copy of security data from the security parent failed

Action:
Contact Administrator.

WC-05321
Failed to delete portal {0} and all its children

Category:
Other

Cause:
Deletion of portal along with children failed

Action:
Contact Administrator.

WC-05322
Failed to retrieve parent portal for the child portal {0}

Category:
Other

Cause:
Failure in retrieving parent portal

Action:
Contact Administrator.

WC-05323
Failed to retrieve child portals for portal {0}

Category:
Other

Cause:
Failure in retrieving child portals

Action:
Contact Administrator.

WC-05324
Failed to set inheritance from parent for portal {0}

Category:
Other

Cause:
Failure in setting the inheritance flag for child portals

Action:
Contact Administrator.

WC-05370
Failed to retrieve root portal for portal {0}

Category:
Other

Cause:
Failure in retrieving root portal

Action:
Contact Administrator.

36

WCC-ADF-10000 to WCC-ADF-30002

WCC-ADF-10000
An internal error occurred.

Category:
Other

Cause:
An internal error occurred.

Action:
Report the error details to Oracle Support Services.

WCC-ADF-10001
File not found: {0}

Category:
Files

Cause:
There was no file at the specified path.

Action:
Correct the path or create the missing file.

WCC-ADF-10002
Invalid file name: {0}

Category:
Files

Cause:
The file name is invalid.

Action:
Check the file name, it may contain reserved characters.

WCC-ADF-10003
Error executing the 'toString' method: {0}

Category:
Other

Cause:
The method 'toString' threw an exception.

Action:
Review the error reported in the chained exception.

WCC-ADF-10004
The type '{0}' could not be converted to '{1}'.

Category:
Programmatic

Cause:
The conversion between two types failed.

Action:
Ensure the type conversion is valid.

WCC-ADF-10005
Item not found: {0}

Category:
Programmatic

Cause:
An item with the specified primary key could not be found.

Action:
Verify that the primary key matches that of an existing item.

WCC-ADF-10006
Initialize user data cache: {0} entries, {1} milliseconds

Category:
Programmatic

Cause:

Action:

WCC-ADF-10007
Invalid value for Java system property {0}: {1}

Category:
Configuration

Cause:
The Java system property had an invalid value.

Action:
Review and correct the value

WCC-ADF-10008
Unable to connect profiler: {0}

Category:
Logging

Cause:
The profiler could not connect to the specified hostname and port.

Action:
Ensure a profiler client is running on that hostname and port

WCC-ADF-10009
Profiler connected: {0}

Category:
Logging

Cause:

Action:

WCC-ADF-10010
Profiler disconnected

Category:
Logging

Cause:

Action:

WCC-ADF-10200
Localization key '{0}' was not found in '{1}'.

Category:
Logging

Cause:
An internal warning occurred.

Action:
Report the warning to Oracle Support Services

WCC-ADF-10201
Message key was not found. Parameters: {0} {1} {2} {3} {4} {5}

Category:
Logging

Cause:
An internal warning occurred.

Action:
Report the warning to Oracle Support Services

WCC-ADF-10202
Log message requires localization due to the log level: {0}

Category:
Logging

Cause:
An internal warning occurred.

Action:
Report the warning to Oracle Support Services

WCC-ADF-10203
Error initializing localization preferences for mode: {0}

Category:
Other

Cause:
Localization preferences for the given mode could not be initialized.

Action:
Review the error reported in the chained exception.

WCC-ADF-10400
The cause of the exception cannot be set.

Category:
Other

Cause:
The exception already contains a cause. It could not be updated to this cause.

Action:
The cause is logged. No action required.

WCC-ADF-10401
Server error cannot be mapped: '{0}' '{1}'

Category:
Programmatic

Cause:
This error is not handled by the UI client.

Action:
Report the details of the issue to Oracle Support Services.

WCC-ADF-10600
The XML document could not be parsed.

Category:
Files

Cause:
The XML document is not valid and/or well formed.

Action:
Review and correct the XML document.

WCC-ADF-10601
Node '{0}' has more than one child element named '{1}'.

Category:
Files

Cause:
The XML document was not valid.

Action:
Review and correct the XML document.

WCC-ADF-10602
Node '{0}' has more than one text child.

Category:
Files

Cause:
The XML document was not valid.

Action:
Review and correct the XML document.

WCC-ADF-10700
Application configuration from wcc-adf-config in adf-config.xml or MDS override: {0}

Category:
Configuration

Cause:

Action:

WCC-ADF-10701
Temporary directory does not exist: {0}

Category:
Configuration

Cause:
The specified temporary directory did not exist.

Action:
Specify a valid and readable/writable temporary directory in the configuration.

WCC-ADF-10702
The application configuration property '{0}' has an invalid value: '{1}'

Category:
Configuration

Cause:
The application configuration property has an invalid value.

Action:
Consult the documentation and specify a valid value.

WCC-ADF-10703
It is strongly recommended to set the \'applicationUrl\' configuration property in the form \'https://host[:port]\'

Category:
Configuration

Cause:
Oracle strongly recommends setting the 'applicationUrl' property to a secure (https) URL.

Action:
Specify a secure (https) URL value.

WCC-ADF-10801
Invalid WccInstance name: {0}

Category:
Configuration

Cause:
A WccInstance with the specified name could not be found.

Action:
Review and correct the WccInstance name.

WCC-ADF-10802
Invalid configuration parameter for WccInstance '{0}'. Parameter: {1}={2}

Category:
Configuration

Cause:
A WccInstance configuration parameter was not correct.

Action:
Review and correct the WccInstance configuration parameter.

WCC-ADF-10900
Required feature is not enabled on the WebCenter Content Server instance '{0}'. Feature: '{1}', Minimum level: {2}

Category:
Configuration

Cause:
A required feature was not enabled on the WebCenter Content Server instance, or the feature level did not meet the minimum requirement.

Action:
Enable the required feature on the WebCenter Content Server instance and ensure the feature is at the minimum required level.

WCC-ADF-10901
If the workflow feature is to be used, it is recommended to enable the feature 'WfDbInQueue' by setting the 'config.cfg' option 'UseDatabaseWfInQueue=1' on the WebCenter Content Server instance '{0}'.

Category:
Configuration

Cause:
A recommended feature on the WebCenter Content Server should be enabled if the workflow feature is to be used..

Action:
Enable the required feature on the WebCenter Content Server instance if the workflow feature is to be used.

WCC-ADF-10902
Required Content Server feature has been enabled. The content server must be restarted before the configuration changes will take place.

Category:
Configuration

Cause:
After enabling the required content server feature, the content server must be restarted.

Action:
The content server must be restarted before the configuration changes will take place.

WCC-ADF-11000
Connection '{0}' could not be created for instance '{1}'.

Category:
Requests/Responses

Cause:
An error occurred while attempting to create the connection.

Action:
Review the connection configuration and the error reported in the chained exception.

WCC-ADF-11001
IdcContext could not be created for user '{0}', connection '{1}', instance '{2}'.

Category:
Requests/Responses

Cause:
An error occurred while attempting to create the user IdcContext.

Action:
Review the connection configuration and the error reported in the chained exception.

WCC-ADF-11002
Connection created: instance '{0}', connection '{1}', server URL '{2}', admin user '{3}'

Category:
Configuration

Cause:

Action:

WCC-ADF-11003
RIDC Client Library Version: {0}

Category:
Configuration

Cause:

Action:

WCC-ADF-11004
Credential could not be fetched.

Category:
Configuration

Cause:
An error occurred while fetching the credentials.

Action:
Review the credential access permission and the error reported in the chained exception.

WCC-ADF-11005
Credential user '{0}' fetched successfully from connection architecture layer.

Category:
Configuration

Cause:

Action:

WCC-ADF-11006
Connection architecture mbean could not be found.

Category:
Configuration

Cause:
An error occurred while getting the credential username from connection architecture mbean.

Action:
Review the error reported in the chained exception.

WCC-ADF-11400
Error executing WebCenter Content service '{0}'.

Category:
Requests/Responses

Cause:
An error occurred while executing a WebCenter Content service.

Action:
Review the error reported in the chained exception.

WCC-ADF-11401
Error executing WebCenter Content service '{0}': {1} (status code: {2}, message key: {3})

Category:
Requests/Responses

Cause:
An error occurred while executing a WebCenter Content service.

Action:
Review the error message.

WCC-ADF-11402
'{0}' could not be converted to RIDC string.

Category:
Other

Cause:
An internal error occurred.

Action:
Report the details of this error Oracle Support Services.

WCC-ADF-11403
RIDC string '{0}' could not be converted to type '{1}'.

Category:
Other

Cause:
An internal error occurred.

Action:
Report the details of this error Oracle Support Services.

WCC-ADF-11404
Unsupported data type: {0}

Category:
Programmatic

Cause:
An attribute definition specified an unsupported data type.

Action:
Review and correct the attribute definition.

WCC-ADF-11420
The Content Server request has timed out, but the operation should continue to run on the server.

Category:
Requests/Responses

Cause:
The Content Server request didn't return a response before the RIDC socket read timeout expired.

Action:
The Content Server request was not aborted, and the operation may continue to run after the timeout. No action required.

WCC-ADF-11600
Operation cannot target more than one WccInstance.

Category:
Programmatic

Cause:
The requested operation targeted two or more WccInstances.

Action:
Target a single WccInstance with the operation.

WCC-ADF-11800
File system operation failed on file or directory: {0}

Category:
Files

Cause:
A file system operation failed on the specified file or directory.

Action:
Check the underlying error and file system permissions by the process attempting the operation.

WCC-ADF-11801
File or directory cannot be deleted: {0}

Category:
Files

Cause:
The specified file or directory could not be deleted.

Action:
Check file system permissions for the process attempting to perform the delete.

WCC-ADF-11802
File or directory cannot be created: {0}

Category:
Files

Cause:
The specified file or directory could not be created.

Action:
Check file system permissions for the process attempting to perform the delete.

WCC-ADF-11803
The file cannot be moved from '{0}' to '{1}'.

Category:
Files

Cause:
The specified file could not be moved.

Action:
Check file system permissions for the process attempting to perform the operation.

WCC-ADF-11804
The uploaded file cannot be larger than {0}.

Category:
Files

Cause:
The uploaded file was larger than the maximum allowed.

Action:
Reduce the file size and try the upload again.

WCC-ADF-11805
The following HTTP error occured while transfering file content: {0}

Category:
Requests/Responses

Cause:
An HTTP error occured while transfering file content.

Action:
Examine the HTTP error code, message, and the server state and logs.

WCC-ADF-11806
The uploaded file cannot be empty.

Category:
Files

Cause:
The uploaded file was empty.

Action:
Upload a non-zero length file.

WCC-ADF-11807
The content of one or more documents was not available, possibly due to a system error or because your session was idle for too long.

Category:
Files

Cause:
The uploaded file token was not found.

Action:
Re-try the upload.

WCC-ADF-11808
The temporary directory structure '{0}' has been tampered with. Ensure the application configuration property 'temporaryDirectory' points to a secure filesystem.

Category:
Files

Cause:
The temporary directory structure has been tampered with.

Action:
Ensure the application configuration property 'temporaryDirectory' points to a secure filesystem.

WCC-ADF-12411
Could not retrieve information for user '{0}'.

Category:
Requests/Responses

Cause:
An error occurred while fetching this user's information.

Action:
If this error occurs multiple times for the same user, report it to Oracle Support Services.

WCC-ADF-12416
An item with the specified identifier does not exist, or cannot be accessed due to insufficient privileges.

Category:
Requests/Responses

Cause:
The specified item did not exist or could not be accessed.

Action:
Specify an existing item you have access to.

WCC-ADF-12417
An item with the specified name already exists.

Category:
Requests/Responses

Cause:
The specified item name matched an existing name.

Action:
Specify an item name that does not already exist.

WCC-ADF-12418
You do not have sufficient privileges to access an item or perform the operation.

Category:
Requests/Responses

Cause:
The user had insufficient privileges to perform the operation.

Action:
Perform the operation as a user with sufficient privileges.

WCC-ADF-12419
The folder is not empty.

Category:
Requests/Responses

Cause:
The operation was not performed on an empty folder as expected.

Action:
Perform the operation on an empty folder.

WCC-ADF-12420
You must be authenticated and have sufficient privileges to perform the operation.

Category:
Requests/Responses

Cause:
The user attempting the operation had insufficient privileges, or was unauthenticated.

Action:
Perform the operation as an authenticated user with sufficient privileges.

WCC-ADF-12421
The name must not contain any reserved characters such as : / \ * " < > | ?

Category:
Requests/Responses

Cause:
The name contained one or more illegal characters.

Action:
Choose a name that does not include any illegal characters.

WCC-ADF-12422
The name must not start or end with whitespace.

Category:
Requests/Responses

Cause:
The specified name started and/or ended with whitespace.

Action:
Choose a name that does not start or end with whitespace.

WCC-ADF-12423
The name is {0} characters too long.

Category:
Requests/Responses

Cause:
The specified name was too long.

Action:
Choose a shorter name.

WCC-ADF-12424
The name is reserved by the system.

Category:
Requests/Responses

Cause:
The specified name matched a reserved system name.

Action:
Choose a different name.

WCC-ADF-12425
The name must not contain consecutive spaces.

Category:
Requests/Responses

Cause:
The name contains consecutive spaces.

Action:
Choose a name that does not contain consecutive spaces.

WCC-ADF-12430
You do not have permission to perform this operation with the specified metadata.

Category:
Requests/Responses

Cause:
The user did not have permission to perform the operation with the specified metadata.

Action:
Modify the metadata or perform the operation as a user with sufficient privileges.

WCC-ADF-12431
A document with the specified Document ID already exists.

Category:
Requests/Responses

Cause:
The specified Document ID matched the Document ID of a document that already exists.

Action:
For new documents, choose a Document ID that does not already exist.

WCC-ADF-12432
The expiration date cannot be before the release date.

Category:
Requests/Responses

Cause:
The expiration date cannot be before the release date.

Action:
Choose an expiration date after the release date.

WCC-ADF-12433
You would not have Write access to the Access Control List.

Category:
Requests/Responses

Cause:
The user would not have Write access to the Access Control List.

Action:
Grant Write access to the Access Control List.

WCC-ADF-12434
You would not have Admin access to the Access Control List.

Category:
Requests/Responses

Cause:
The user would not have Admin access to the Access Control List.

Action:
Grant Admin access to the Access Control List.

WCC-ADF-12435
There was an error executing the search, possibly because the search expression was invalid.

Category:
Requests/Responses

Cause:
The search query cannot be executed as specified.

Action:
Check the search term syntax and try again.

WCC-ADF-12436
The value entered for '{0}' exceeds {1} characters, the maximum length allowed for this field.

Category:
Requests/Responses

Cause:
The value entered for the field is too long.

Action:
Enter a value up to the maximum allowed length.

WCC-ADF-12437
You do not have Write access to folder '{0}'.

Category:
Requests/Responses

Cause:
The user does not have write access to the folder.

Action:
Select a folder that has write access.

WCC-ADF-12438
A null value cannot be propagated for field '{0}'.

Category:
Requests/Responses

Cause:
The value entered for the field may not be null.

Action:
Enter a non-null value.

WCC-ADF-12439
Item '{0}' cannot be revised because the source and destination have different types.

Category:
Requests/Responses

Cause:
The source and destination items have different types.

Action:
Manually resolve the conflict by deleting or renaming the destination item.

WCC-ADF-12440
You do not have sufficient privileges to access the content account '{1}'.

Category:
Requests/Responses

Cause:
The user does not have sufficient privileges to access the specified account.

Action:
Select an account that gives the user sufficient privileges.

WCC-ADF-12441
The document is not in workflow.

Category:
Requests/Responses

Cause:
The user is trying to approve or reject a document that is not in workflow.

Action:
Refresh the document information.

WCC-ADF-12442
You are not a reviewer for workflow step '{0}'.

Category:
Requests/Responses

Cause:
The user is not a reviewer for the current workflow step.

Action:
Refresh the document information.

WCC-ADF-12443
The document is not in a workflow review step.

Category:
Requests/Responses

Cause:
The document is not in a workflow review step.

Action:
Refresh the document information.

WCC-ADF-12444
You are not a contributor for workflow step '{0}'.

Category:
Requests/Responses

Cause:
The user is not a contributor for the current workflow step.

Action:
Refresh the document information.

WCC-ADF-12470
You selected a revision that is not the latest revision of the document.

Category:
Requests/Responses

Cause:
The user selected a revision other than the latest revision of the document.

Action:
Refresh the document information, select the latest revision and retry the operation.

WCC-ADF-12471
You selected a document that is not checked out or a revision that is not the latest revision of the document.

Category:
Requests/Responses

Cause:
The user selected a revision other than the latest revision of the document or the document is not checked out.

Action:
Refresh the document information, select the latest revision and retry the operation.

WCC-ADF-12472
You may not move content between the two library or folder types.

Category:
Requests/Responses

Cause:
The user is attempting to move content between two types of libraries or folders that do not allow the operation.

Action:
Select a destination compatible with the source and re-try the move operation.

WCC-ADF-12473
You may not move or copy a document pending initial workflow contribution.

Category:
Requests/Responses

Cause:
The user is attempting to move or copy a document pending initial workflow contribution.

Action:
Try the operation again after the document is out of the initial workflow contribution.

WCC-ADF-12474
You entered the invalid value '{0}' for the Revision field.

Category:
Requests/Responses

Cause:
The value entered for the Revision field is not valid.

Action:
Enter a valid value.

WCC-ADF-12475
The document is checked out by another user.

Category:
Requests/Responses

Cause:
The user is attempting to check out or check in a document that is checked out by another user.

Action:
Try the operation again after the document is no longer checked out by another user.

WCC-ADF-12476
The folder '{0}' could not be renamed.

Category:
Requests/Responses

Cause:
An error occurred while renaming a folder.

Action:
Some system folders cannot be renamed.

WCC-ADF-12480
You may not copy or move a folder into itself or its descendant.

Category:
Requests/Responses

Cause:
Copying or moving a folder into itself or its descendant is prohibited.

Action:
Select a destination for copy or move that is neither the source folder nor its descendant.

WCC-ADF-12490
A value is required for field '{0}'.

Category:
Requests/Responses

Cause:
The required field does not have a value.

Action:
Enter a value for the required field. If the required field is hidden, make sure it has a default valued defined in Content Server.

WCC-ADF-12495
The item cannot be accessed because it was moved to Trash.

Category:
Requests/Responses

Cause:
An attempt was made to access a Trash item from outside the context of the Trash listing.

Action:
Refresh the page where the item was displayed, and verify that the item is no longer displayed after the page has reloaded.

WCC-ADF-12800
The cloud folder could not be found within the Oracle Documents Cloud Service. The folder may be missing, or the cloud service may be unavailable.

Category:
Requests/Responses

Cause:
Its linked folder in Oracle Documents Cloud Service no longer exists or is not accessible.

Action:
Verify its counterpart in Oracle Documents Cloud Service still exists and is accessible.

WCC-ADF-12801
The action failed in Oracle Documents Cloud Service.

Category:
Requests/Responses

Cause:
The action could not be performed in Oracle Documents Cloud Service.

Action:
Content Server doesn't provide much details on this error. Report the error to Oracle Support Services.

WCC-ADF-12802
The cloud folder cannot be shared with your Oracle Documents account.

Category:
Requests/Responses

Cause:
You don't have a personal account for Oracle Documents Cloud Service, or the e-mail address in your WebCenter Content preferences doesn't correspond with your Oracle Documents account.

Action:
Make sure you have a personal account in Oracle Documents Cloud Service, and that your WebCenter Content e-mail address setting corresponds with that account.

WCC-ADF-12803
This file type is not supported by Oracle Documents Cloud Service.

Category:
Requests/Responses

Cause:
This file type is not allowed to be stored in the Oracle Documents repository.

Action:
Don't attempt to copy files of this type to Oracle Documents Cloud Service.

WCC-ADF-12804
This cloud folder has already been shared with your Oracle Documents account.

Category:
Requests/Responses

Cause:
If a cloud folder is currently shared with a particular account, it cannot be shared with that same account again.

Action:
Don't attempt to share this cloud folder with your Oracle Documents account again unless the existing share has been removed.

WCC-ADF-12805
You're already the owner of this cloud folder. Sharing it with your own Oracle Documents account is not a valid operation.

Category:
Requests/Responses

Cause:
The owner of a cloud folder can't share that folder with their own account.

Action:
Don't attempt to share this cloud folder with your Oracle Documents account.

WCC-ADF-14001
The number of accounts assigned to you exceeds the maximum number of accounts allowed by this query, so the listing may not include all the items you have access to. Note that you can still perform operations (such as uploading content or creating folders) for all your

accounts, even though the results of those operations may not be visible in the listing if the account is among those truncated from the query.

Category:
Requests/Responses

Cause:
The number of accounts assigned exceeds the maximum allowed by the query.

Action:
Report the issue to your system administrator.

WCC-ADF-20200
The type '{1}' was unexpected for field '{0}' (treating as STRING).

Category:
Data

Cause:
A field had an unexpected data type.

Action:
Report the details of this warning Oracle Support Services.

WCC-ADF-30000
The Faces Servlet filter '{0}' is not configured correctly.

Category:
Configuration

Cause:
The Faces Servlet filter was not configured correctly.

Action:
Check the documentation for the proper filter configuration.

WCC-ADF-30001
Cannot find UI component '{0}'.

Category:
Logging

Cause:

Action:

WCC-ADF-30002
WCCADF mbean could not be registered.

Category:
Configuration

Cause:
An error occurred while registering the WCCADF mbean.

Action:
Review the error reported in the chained exception.

37

WCS-03051 to WCS-90200

WCS-03051
No event is selected.

Category:
Other

Cause:
There was invalid or missing information in the connection.xml or adf-config.xml file.

Action:
Verify that the connections.xml and adf-config.xml file contains a valid entry with the correct connection information.

WCS-03052
event date validation error

Category:
Other

Cause:
An invalid date or time was selected for the event.

Action:
Verify the date and time.

WCS-03053
No upcoming events were found.

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Portal Events service, or the adapter was not defined.

Action:
Verify that the connections.xml file contains a valid connection for the Portal Events service, and the Portal Events server is running

WCS-03101
The Events service is not able to acquire an adapter from the server.

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Personal Events service, or the adapter was not defined.

Action:
Verify that the connections.xml file contains a valid connection entry for the Personal Events service, and the specified adapter is defined.

WCS-03102
The Events service is unavailable.

Category:
Other

Cause:
The connections.xml file either did not contain a valid connection entry for the Personal Events service, or it was missing the entry for Personal Events with the state attribute set to default.

Action:
Verify that the connections.xml file contains a valid connection entry for the Personal Events service, and the Personal Events server is running.

WCS-03103
Data query in Personal Events service failed

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Personal Events service, or the Personal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Personal Events service, and the Personal Events server is running.

WCS-03104
Create event in Personal Events service failed

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Personal Events service, or the Personal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Personal Events service, and the Personal Events server is running.

WCS-03105
Update event in Personal Events service failed

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Personal Events service, or the Personal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Personal Events service, and the Personal Events server is running.

WCS-03106
Delete event in Personal Events service failed

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Personal Events service, or the Personal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Personal Events service, and the Personal Events server is running.

WCS-03107
failure to send event mail in Personal Events service

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection for the Mail service, or the Mail server was down.

Action:
Verify that the connections.xml file contains a valid connection for the Mail service, and that the Mail server is running.

WCS-03108
failure to retrieve online meeting

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Conference service, or the Conference server was down.

Action:
Verify that the connections.xml file contains a valid connection for the Conference service, and the Conference server is running.

WCS-03109
failure to retrieve personal event list

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Personal Events service, or the Personal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Personal Events service, and the Personal Events server is running.

WCS-03110
failure to retrieve personal event detail

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Personal Events service, or the Personal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Personal Events service, and the Personal Events server is running.

WCS-03111
The Personal Events service credential is not configured properly.

Category:
Other

Cause:
The Personal Events service credential was not configured properly.

Action:
Verify that the Personal Events service credential is correct, and try again.

WCS-03112
The Personal Events service is not properly configured.

Category:
Other

Cause:
The Personal Events service was not properly configured in connections.xml.

Action:
Verify that the connections.xml file contains a valid entry for the Personal Events service.

WCS-03113
The Personal Events server is not available.

Category:
Other

Cause:
The Personal Events server was not available.

Action:
Verify that the connections.xml file contains a valid entry for the Personal Events service, and the Personal Events server is running.

WCS-03114
failure to send personal event

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection for the Mail service, or the Mail server was down.

Action:
Verify that the connections.xml file contains a valid connection for the Mail service, and the Mail server is running.

WCS-03201
The Events service is not able to acquire an adapter for an Events server.

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Portal Events service.

Action:
Verify that the connections.xml file contains a valid connection entry for the Portal Events service.

WCS-03202
The Events service is unavailable.

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Portal Events service, or the Portal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Portal Events service, and the Portal Events server is running.

WCS-03203
Data query in Events service failed

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Portal Events service, or the Portal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Portal Events service, and the Portal Events server is running.

WCS-03204
Create event in Events service failed

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Portal Events service, or the Portal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Portal Events service, and the Portal Events server is running.

WCS-03205
Update event in Events service failed

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Portal Events service, or the Portal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Portal Events service, and the Portal Events server is running.

WCS-03206
Delete event in Events service failed

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Portal Events service, or the Portal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Portal Events service, and the Portal Events server is running.

WCS-03207
Send event mail in Events service failed

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection for the Mail service, or the Mail server was down.

Action:
Verify that the connections.xml file contains a valid connection for the Mail service, and Mail server is running.

WCS-03208
The changes to the event cannot be saved.

Category:
Other

Cause:
The event was modified or deleted by another user after the event was retrieved.

Action:
Refresh the Events task flow to view changes, and try again.

WCS-03209
Cannot create the category

Category:
Other

Cause:
The category could not be created because a category of the same name already exists.

Action:
Select the existing category.

WCS-03210
cannot add the portal event to the personal calendar

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Personal Events service, or the Personal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Personal Events service, and the Personal Events server is running.

WCS-03211
cannot add the portal event to the personal calendar

Category:
Other

Cause:
The Personal Events service was not configured properly in connections.xml or the Personal Events service is down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Personal Events service, and the Personal Events server is running.

WCS-03212
cannot add the portal event to the personal calendar

Category:
Other

Cause:
The credential for the Personal Events service was not configured properly.

Action:
Verify that the credential for the Personal Events service is correct.

WCS-03213
Failure to create category

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Portal Events service, or the Portal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Portal Events service, and the Portal Events server is running.

WCS-03214
failure to retrieve categories

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Portal Events service, or the Portal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Portal Events service, and the Portal Events server is running.

WCS-03215
failure to retrieve portal event list

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Portal Events service, or the Portal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Portal Events service, and the Portal Events server is running.

WCS-03216
failure to retrieve portal event detail

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Portal Events service, or the Portal Events server was down.

Action:
Verify that the connections.xml file contains a valid connection entry for the Portal Events service, and the Portal Events server is running.

WCS-03217
failure to check the relationship for the event

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Relationship service,or the Relationship service was down.

Action:
Verify that the connections.xml file contains a valid entry for the Relationship service, the Relationship service is running.

WCS-03218
failure to save the display mode preference

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Preferences service, or the Preferences service was down.

Action:
Verify that the connections.xml file contains a valid entry for the Preferences service, and the Preferences service is running.

WCS-03219
failure to change the repeat attributes

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry for the Events service, or the Events service was down.

Action:
Verify that the connections.xml file contains a valid entry for the Events service, and the Events service is running.

WCS-03220
The event was deleted by another user after you retrieved it. Refresh the Events task flow to see the changes if necessary.

Category:
Other

Cause:
The event was deleted by another user after you retrieved it.

Action:
Refresh the Events task flow to view changes, and try again.

WCS-03221
The event was updated by another user after you retrieved it. Refresh the Events task flow to see the changes if necessary.

Category:
Other

Cause:
The event was updated by another user after you retrieved it.

Action:
Refresh the Events task flow to view changes, and try again.

WCS-03222
You do not have permission to update this event or your permission to update this event is revoked. Refresh the Events task flow to see the changes if necessary.

Category:
Other

Cause:
You do not have permission to update this event or your permission to update this event is revoked.

Action:
Refresh the Events task flow to view changes, and try again.

WCS-03223
You do not have permission to view this event or your permission to view this event is revoked. Refresh the Events task flow to see the changes if necessary.

Category:
Other

Cause:
You do not have permission to view this event or your permission to view this event is revoked.

Action:
Refresh the Events task flow to view changes, and try again.

WCS-03224
You do not have permission to create the event or your permission to create the event is revoked. Refresh the Events task flow to see the changes if necessary.

Category:
Other

Cause:
You do not have permission to create this event or your permission to create this event is revoked.

Action:
Refresh the Events task flow to view changes, and try again.

WCS-03225
You do not have permission to delete the event or your permission to delete the event is revoked. Refresh the Events task flow to see the changes if necessary.

Category:
Other

Cause:
You do not have permission to delete this event or your permission to delete this event is revoked.

Action:
Refresh the Events task flow to view changes, and try again.

WCS-03226
You do not have permission to manage the event or your permission to manage the event is revoked. Refresh the Events task flow to see the changes if necessary.

Category:
Other

Cause:
You do not have permission to manage this event or your permission to manage this event is revoked.

Action:
Refresh the Events task flow to view changes, and try again.

WCS-03227
Event not found.

Category:
Other

Cause:
The event doesn't exist or was deleted.

Action:
Refresh the Events task flow to view changes, and try again.

WCS-03228
The Events service is currently disabled, preventing you from performing this operation. Contact your administrator.

Category:
Other

Cause:
The Events service is currently disabled.

Action:
Contact your administrator. Enable the Events service.

WCS-03301
The Web Conference service is unavailable.

Category:
Other

Cause:
Either the connections.xml file did not contain a valid connection entry, or the adapter was not defined in the adf-config.xml file.

Action:
Verify that the connections.xml file contains a valid connection entry, and the specified adapter is defined in the adf-config.xml file.

WCS-03302
The Web Conference service is unavailable.

Category:
Other

Cause:
The connections.xml file either did not contain a valid connection entry or the entry for conference service with the state attribute set to default was missing.

Action:
Verify that the connections.xml file contains a valid connection entry and that the conference server is running.

WCS-03303
failure to query data in WebCenter Conference service

Category:
Other

Cause:
There was an issue with the connections.xml file, or the Conference server was down.

Action:
Verify that the connections.xml file contains a valid connection entry and that the Conference server is running.

WCS-03304
failure to create conference in WebCenter Conference service

Category:
Other

Cause:
There was an issue with the connections.xml file, or the Conference server was down.

Action:
Verify that the connections.xml file contains a valid connection entry and that the Conference server is running.

WCS-03305
failure to update conference in WebCenter Conference service

Category:
Other

Cause:
There was an issue with the connections.xml file, or the Conference server was down.

Action:
Verify that the connections.xml file contains a valid connection entry and that the Conference server is running.

WCS-03306
failure to delete conference in WebCenter Conference service

Category:
Other

Cause:
There was an issue with the connections.xml file, or the Conference server was down.

Action:
Verify that the connections.xml file contains a valid connection entry and that the Conference server is running.

WCS-03307
failure to retrieve personal meetings

Category:
Other

Cause:
There was an issue with the connections.xml file, or the Conference server was down.

Action:
Verify that the connections.xml file contains a valid connection entry and that the Conference server is running.

WCS-03308
The Conference service is not properly configured.

Category:
Other

Cause:
The Conference service was not properly configured in connections.xml.

Action:
Verify that the connections.xml file contains a valid entry for the Conference service.

WCS-03309
The Conference service is properly not configured.

Category:
Other

Cause:
The Conference service was not configured in connections.xml.

Action:
Verify that the connections.xml file contains a valid entry for the Conference service.

WCS-03310
The Conference service is not properly configured.

Category:
Other

Cause:
The ambiguous connections of Conference service were found in connections.xml.

Action:
Verify that the connections.xml file contains a valid entry for the Conference service.

WCS-04001
unable to resolve the name {0}

Category:
Other

Cause:
The object with the given name could not be found.

Action:
Check the JNDI configuration or the context passed.

WCS-04002
ADFConfig does not contain adf-collaboration-config details with namespace: {0}.

Category:
Other

Cause:
The collaboration configuration tag 'adf-collaboration-config' might have been missing in ADFConfig.

Action:
Ensure that the adf-config.xml file contains the adf-collaboration-config tag.

WCS-04003
No adapter found for service {0}

Category:
Other

Cause:
No adapter configuration found or the implementation class could not be loaded.

Action:
Ensure adapter is configured properly or change the SessionFactory to override the default behavior.

WCS-04004
unable to load the class {0}

Category:
Other

Cause:
The class named in the error message was not available in the class path.

Action:
Check the class path and ensure this class is available.

WCS-04005
unable to load the class {0}, due to: {1}

Category:
Other

Cause:
Either the class named in the error message was not available in the class path or it could not be instantiated.

Action:
Check the logs for more details. Contact Oracle Support Services.

WCS-04006
ADFConfig {0} {1} does not contain the required attribute {1}.

Category:
Other

Cause:
The required attribute was missing from the configuration.

Action:
Ensure that the required attribute is added to the configuration.

WCS-04007
The attachment size is too large to be consumed.

Category:
Other

Cause:
The storage quota was exceeded.

Action:
Select a different attachment with a smaller size.

WCS-04008
The attachment type is not supported.

Category:
Other

Cause:
The attachment type was not supported.

Action:
Try with a different MIME type.

WCS-04009
The attachment cannot be found.

Category:
Other

Cause:
The attachment was not readable.

Action:
Try a different attachment.

WCS-04010
failure to create, update, or fetch the service configuration file {0}, due to: {1}

Category:
Other

Cause:
One of the following was the cause: There was a concurrent modification by another user; there was an MDS I/O exception; the metadata was not found; a validation error occurred; or the update was not supported.

Action:
Contact Oracle Support Services.

WCS-04011
unable to find the service configuration file {0}, due to: {1}

Category:
Other

Cause:
The service was not provisioned for this portal.

Action:
Provision this service or contact the system administrator.

WCS-04012
unable to find the credentials for user {0}

Category:
Other

Cause:
The credentials were either not supplied, or were invalid.

Action:
Supply credentials using the External Application configured for the service.

WCS-04013
failure to authenticate the user {0}, due to: {1}

Category:
Other

Cause:
There was a failure while connecting to server, or the credentials were invalid.

Action:
Ensure the credentials are supplied and are valid.

WCS-04014
no connections available for: {0}

Category:
Other

Cause:
There are no connections defined for this connection type.

Action:
At least one connection must be defined for this connection type.

WCS-04015
There are multiple connections defined for the connection type {0}, but no default connection is specified.

Category:
Other

Cause:
Multiple connections of this type were defined, but the default connection was not specified.

Action:
Select the appropriate connection for this type and mark it as the default.

WCS-04016
unable to look up connection with name {0}

Category:
Other

Cause:
Either the connection name was wrong or the connection was deleted.

Action:
Verify the name of the connection supplied and also ensure that the connection with this name is available.

WCS-04017
failure to create session instance for: {0}

Category:
Other

Cause:
An instantiation exception occurred for the session class. Either this class was not a valid class or it could not be loaded from the class path.

Action:
Verify that the session class supplied is a valid class, and that it is available in the class path.

WCS-04018
failure to create session for {0}, due to: {1}

Category:
Other

Cause:
Either the required configuration was missing or class was not found.

Action:
Verify that the session class supplied is a valid class, and that it is available in the class path.

WCS-04019
There are multiple adapters for the session {0}, but the default adapter is not specified.

Category:
Other

Cause:
Multiple adapters were defined for this session type, but the default adapter was not specified in the connection.

Action:
Update the connection and ensure that the adapter name is specified (ensure that the "adapter.name" property exists).

WCS-04020
No adapter found with name {0}.

Category:
Other

Cause:
Adapter not found with the given name.

Action:
Ensure the adapter with this name configured in the adf-config.xml file.

WCS-04021
Not an instance of {1} : {0}

Category:
Other

Cause:
Supplied class is not an instance of SessionManager class.

Action:
Check the service configuration property "session.manager.class".

WCS-04022
The service is unavailable.

Category:
Other

Cause:
Cannot establish connection to the server, either the server is down or the connect details are wrong.

Action:
Contact system administrator.

WCS-04023
Cache not available.

Category:
Other

Cause:
Cache is not initialized.

Action:
Contact system administrator.

WCS-04024
unable to find object {0} in the cache

Category:
Other

Cause:
The object was either not cached or it had expired.

Action:
Ensure that the object is cached.

WCS-04025
Session not initialized {0}.

Category:
Other

Cause:
Either initialize method on the session is not invoked or initialization has failed.

Action:
Check logs for more details or Contact system administrator.

WCS-04026
session instance acquired is null from SessionFactory: {0}

Category:
Other

Cause:
SessionFactory returned null session instance. Wrong factory implementation.

Action:
Check the SessionFactory implementation for more details or contact the system administrator.

WCS-04027
Session Factory class not defined.

Category:
Other

Cause:
Either the service-config for the session is missing or "session.factory.class" property is missing.

Action:
Check the service-config.xml for the given session type exists and "session.factory.class" property is defined with a qualified class name that is available in the classpath. Contact system administrator for more information.

WCS-04030
System user session is requested from session {0}, but administrator user name is not defined in the connection nor in adf-config.

Category:
Other

Cause:
Missing "admin.user" property from connection and/or adf-config.xml.

Action:
Ensure that either the connection or ADF service-config contains a property called "admin.user" with a valid administrator user.

WCS-04031
Unexpected error occurred, due to : {0}

Category:
Other

Cause:
An unexpected server exception occurred.

Action:
Contact the system administrator.

WCS-04032
Could not get access to cache object.

Category:
Other

Cause:
API should be invoked only for getting access to the root cache.

Action:
Try using correct API.

WCS-04033
Invalid cache name: {0}.

Category:
Other

Cause:
Cache name supplied is either empty or null.

Action:
Supply valid name for the cache.

WCS-04034
Not able to fetch data due to {0}.

Category:
Other

Cause:
Might be because the backend system is not reachable.

Action:
Try after sometime.

WCS-04035
Session Type for Session instance {0} is null.

Category:
Other

Cause:
Session Factory does not set the SessionType on the Session instance created.

Action:
Check the session factory implementation.

WCS-04036
User not found: {0}.

Category:
Other

Cause:
Unable to find the user with the supplied name in the user repository.

Action:
Check user with the given identity exists in the user repository.

WCS-04037
Supplied class {0} is not an instance of {1}.

Category:
Other

Cause:
Supplied class is not an instance of SessionFactory class.

Action:
Check the adf-config.xml or service-config.xml configuration property "session.factory.class".

WCS-04039
Session Manager instance creation failed for {0}

Category:
Other

Cause:
Either the required configuration is missing or class is not found..

Action:
Check the class supplied is a valid class and its available in the classpath.

WCS-04040
CacheFactory not specified.

Category:
Other

Cause:
CacheFactory instance is not found.

Action:
Set appropriate CacheFactory instance on the Cache class.

WCS-04041
No default or active connection available for: {0}

Category:
Other

Cause:
There is no default or active connection defined for this connection type.

Action:
At least one connection must be defined default or active for this connection type.

WCS-04042
Enterprise role not found: {0}.

Category:
Other

Cause:
Unable to find the enterprise role with the supplied name in the backend server.

Action:
Check group with the given identity exists in the backend server.

WCS-04043
Service is disabled for the current Portal: {0}.

Category:
Other

Cause:
Service is disabled for the current Portal.

Action:
Enable this service or contact the Portal Moderator.

WCS-04201
Error loading relationship service implementation

Category:
Other

Cause:
The relationship service encountered a problem while loading a relationship service implementation.

Action:
Check the stack trace for more information

WCS-04206
Error checking create permission

Category:
Other

Cause:
There was an error loading the relationship security provider.

Action:
Check to make sure that the relationship security provider is properly configured.

WCS-04207
Could not instantiate relationship repository

Category:
Other

Cause:
The relationship service encountered a problem while instantiating the repository.

Action:
Check the stack trace for more information.

WCS-04208
jdbc/WebCenterDS data source not found: {0}

Category:
Other

Cause:
The jdbc/WebCenterDS data source could not be found.

Action:
Ensure that the jdbc/WebCenterDS data source is created.

WCS-04301
Relationship repository is not available.

Category:
Other

Cause:
An error was encountered while checking if the relationship repository was available.

Action:
Check the log for errors that may have caused this.

WCS-04302
Relationship already exists between [sourceApplicationId={0} sourceResourceId={1}] and [targetApplicationId={2} targetResourceId{3}].

Category:
Other

Cause:

Action:

WCS-04303
Resource does not exist [applicationId={0} resourceId={1}].

Category:
Other

Cause:

Action:

WCS-04304
Target resource was not found [targetApplicationId={0} targetResourceId={1}].

Category:
Other

Cause:

Action:

WCS-04305
Relationship was marked as a bi-directional relationship, however no target to source back relationship was found for target [targetApplicationId={0} targetResourceId={1}].

Category:
Other

Cause:

Action:

WCS-04306
Source object was not found [sourceApplicationId={0} sourceResourceId={1}].

Category:
Other

Cause:

Action:

WCS-04401
Exception during event or action

Category:
Other

Cause:
The relationship service encountered a problem while performing an event or action

Action:
Check the application log for more information on the cause

WCS-04403
Could not find relationship service {0}

Category:
Other

Cause:

Action:

WCS-04404
Service {0} threw exception for getViewObject() on RelatedObject {1}

Category:
Other

Cause:

Action:

WCS-04405
linksDetailedPanelWindow is null: cannot add partial target to RequestContext.

Category:
Other

Cause:
The relationship popup task flow is not included in the page.

Action:
Check to make sure the relationship popup task flow is included in the page.

WCS-04406
Cannot get current RichLinksDetailButtonRow.
FacesContext.getCurrentInstance().getRenderKit() returned null for component: {0}

Category:
Other

Cause:

Action:

WCS-04407
Exception while checking for existing links

Category:
Other

Cause:
An error was encountered while checking for existing links.

Action:
Check the application log for more information on the cause.

WCS-04408
Error instantiating RichLinksDetailButtonRow

Category:
Other

Cause:
The relationship service encountered a problem while instantiating a custom component.

Action:
Check the relationship links button component for valid attributes.

WCS-04409
Error instantiating RichLinskDetailMenuItem

Category:
Other

Cause:
The relationship service encountered a problem while instantiating a custom component.

Action:
Check the relationship links menu component for valid attributes.

WCS-04410
Could not find Links Detail Popup in the LinksDetailBean bean

Category:
Other

Cause:
The relationship service encountered a problem while encoding the popup.

Action:
Make sure the links popup task flow is included in the page.

WCS-04412
Attribute value is null for component: {0}

Category:
Other

Cause:
A required attribute value is bound to a null value.

Action:
Make sure the required attributes of this component are bound to non-null values.

WCS-04413
An exception occurred while parsing parameter

Category:
Other

Cause:
A number format exception was encountered while parsing a parameter.

Action:
Make sure the window width/height parameters for launching relationship views are valid numbers.

WCS-04414
Got null from registry for service ID {0}, including all target services: {1}

Category:
Other

Cause:

Action:

WCS-04415
Service {0} returned null for target view object with objectId: {1}.

Category:
Other

Cause:

Action:

WCS-04417
Could not find {0} parameter for the Links Detail taskflow.

Category:
Other

Cause:
The parameter is required for processing links-detail task flow.

Action:
Make sure the parameter is bound to a non-null value.

WCS-04418
User principal is null.

Category:
Other

Cause:
The user principal returned by the security context was null.

Action:
Make sure security is property configured for the application.

WCS-04419
Links components cannot render

Category:
Other

Cause:
The links-detail-popup task flow panelWindow was not found.

Action:
Make sure the view includes the links-detail-popup task flow.

WCS-04420
The image file {0} you tried to select was invalid. Provide a valid image file.

Category:
Other

Cause:
Unable to embed the image as the file is null or invalid.

Action:
Select a valid image file

WCS-04421
The taskflow id {0} was invalid. Provide a valid taskflow id.

Category:
Other

Cause:
Unable to retrieve the taskflow as the id is null or invalid.

Action:
Specify a valid taskflow Id.

WCS-04422
The NewRelatedObject returned from the service {0} was invalid.

Category:
Other

Cause:
Unable to process the returned object.

Action:
Return a valid object for linking.

WCS-04601
unexpected error

Category:
Other

Cause:
An unexpected error occurred for the RTC service.

Action:
Contact Oracle Support Services.

WCS-04602
Unable to load RTC configuration

Category:
Other

Cause:
Connections context could not be acquired.

Action:
Ensure that the connections.xml file is available and valid.

WCS-04603
Unable to load RTC configuration

Category:
Other

Cause:
No RTC (Real-Time Communication) connection was specified.

Action:
Ensure that the property 'selected.connection' for the RTC service's 'service-config' element within the application's adf-config.xml file is available with a valid RTC connection name value.

WCS-04604
Unable to lookup RTC connection {0}

Category:
Other

Cause:
The specified connection name either did not exist or did not resolve to a valid RTC connection.

Action:
Ensure that the property 'selected.connection' for the RTC service's 'service-config' element within the application's adf-config.xml file contains a valid RTC connection name (as defined in the application's connections.xml file).

WCS-04605
Unable to load RTC adapter {0}

Category:
Other

Cause:
The specified RTC adapter name was invalid.

Action:
Ensure that the property 'adapter.name' of the RTC connection is valid and the corresponding adapter definition is available within the RTC 'service-config' element in the application's adf-config.xml file.

WCS-04606
Unable to load RTC adapter {0}

Category:
Other

Cause:
The specified RTC adapter class does not extend from IMPConnection class.

Action:
Ensure that the RTC adapter class extends IMPConnection class and follows its contract.

WCS-04607
Unable to load RTC adapter {0}

Category:
Other

Cause:
The specified RTC adapter class could not be instantiated.

Action:
Ensure that the RTC adapter class extends IMPConnection class and follows its contract.

WCS-04608
Unable to load RTC adapter {0}

Category:
Other

Cause:
The RTC configuration object was null or invalid.

Action:
Ensure that the RTC configuration is valid.

WCS-04610
Unable to create instance of the UserManager implementation class {0}.

Category:
Other

Cause:
The specified user manager class could not be instantiated.

Action:
Ensure that the class exists and can be instantiated with a default constructor.

WCS-04611
Unable to find a valid RTC connection.

Category:
Other

Cause:
No RTC connections were found within the application's connections.xml file.

Action:
Ensure that there is a valid RTC connection defined in the application's connections.xml file.

WCS-04612
Invalid RTC address resolver specified: {0}

Category:
Other

Cause:
Specified address resolver was invalid.

Action:
Ensure that the resolver type is one of DEFAULT, PROFILE_ATTRIBUTE, or CUSTOM.

WCS-04614
Invalid attribute specified for PROFILE address resolver: {0}

Category:
Other

Cause:
The specified profile attribute for the address resolver was invalid.

Action:
Ensure that the 'rtc.address.resolver.mapping' attribute is not null and contains a valid profile attribute.

WCS-04615
Unable to load custom RTC address resolver: {0}

Category:
Other

Cause:
The custom class could not be initialized.

Action:
Ensure that the custom class extends RtcAddressResolver and follows the contract specified by it.

WCS-04616
Unable to load custom RTC address resolver: {0}

Category:
Other

Cause:
No custom class was specified for the CUSTOM type RTC address resolver.

Action:
Ensure that the 'rtc.address.resolver.mapping' attribute is not null and contains a fully qualified and valid class name that extends from the RtcAddressResolver class.

WCS-04619
The RTC address resolver supplied is invalid or null.

Category:
Other

Cause:
The RTC address resolver supplied was invalid or null.

Action:
Ensure that 'rtc.address.resolver.mapping' attribute is not null.

WCS-04620
The domain supplied is invalid or null.

Category:
Other

Cause:
The domain supplied was invalid or null.

Action:
Ensure that the 'domain' attribute is not null or invalid.

WCS-04621
Invalid timeout value specified: {0} Defaulting to {1}

Category:
Other

Cause:
The presence cache timeout value was either null or not a valid number.

Action:
Ensure that the 'rtc.cache.time' attribute is not null and contains a valid number.

WCS-04625
Failed to instantiate IMPSession for the logged-in user.

Category:
Other

Cause:
The adapter class could not be instantiated.

Action:
Ensure that the property 'adapter-class' has been defined for the adapter in the adf-config.xml and is valid.

WCS-04801
Invalid timeout value specified: {0} Defaulting to {1}

Category:
Other

Cause:
The presence cache timeout value was either null or not a valid number.

Action:
Ensure that the 'rtc.cache.time' attribute is not null and contains a valid number.

WCS-04804
Unable to acquire RTC connection for user {0}. RTCService running in dummy mode.

Category:
Other

Cause:
Exception caught while initializing IMPConnection.

Action:
Check the log file for more information.

WCS-04805
Unable to acquire associated external application details.

Category:
Other

Cause:
The external application ID could not be loaded from the RTC connection configuration.

Action:
Ensure that the 'ext.app.id' attribute is not null and refers to a valid external application ID.

WCS-04806
Unable to acquire associated external application details.

Category:
Other

Cause:
The external application was not found for the external application ID.

Action:
Ensure that external application ID refers to a valid external application.

WCS-04851
Failed to generate endpoint to talk to OCS WebService.

Category:
Other

Cause:
The webservice is unreachable.

Action:
Ensure that the OCS connection entry contains the 'base.connection.url' property and points to a valid URL.

WCS-04852
Unable to perform operation {0}

Category:
Other

Cause:
Failed to perform the operation on remote Web service.

Action:
Ensure that the RTC configuration is correct, the remote system is available, and the errors generated in the remote system's logs have been fixed.

WCS-04853
Exception caught while fetching buddy list for user {0}

Category:
Other

Cause:
Failed to retrieve buddy list from the Remote Service.

Action:
Ensure that valid OCS connection entries have been supplied and the server is up.

WCS-04854
Exception caught while fetching presence information using user account {0}

Category:
Other

Cause:
Failed to fetch presence information from the remote service.

Action:
Ensure that valid OCS connection entries have been supplied and the server is up.

WCS-04855
Account field missing from user credentials

Category:
Other

Cause:
Cannot login to server without the account information.

Action:
Ensure that a valid sip address value is supplied as the Account in credentials.

WCS-04856
Connection not defined

Category:
Other

Cause:
Connection is not defined.

Action:
Ensure that the connection is defined.

WCS-04857
External application ID not defined.

Category:
Other

Cause:
The required configuration parameter External Application ID was not found.

Action:
Contact your system Administrator.

WCS-04901
Not initializing RtcAction {0} as it does not extend from RtcAction

Category:
Other

Cause:
Specified class does not extend from RtcAction.

Action:
Ensure that the specified class is a proper subclass of RtcAction.

WCS-04902
Failed to initialize RtcAction {0}

Category:
Other

Cause:
Unable to instantiate the supplied RtcAction subclass.

Action:
Ensure that the specified class is a proper subclass of RtcAction, and provides a default constructor.

WCS-04903
ADFConfig does not contain rtc-config details with namespace : {0}.

Category:
Other

Cause:
The RTC actions tag 'rtcC:actions' might be missing in ADFConfig.

Action:
Ensure adf-config.xml file contains rtcC:actions tag.

WCS-04904
Cannot process call request : User Profile for user {0} not found

Category:
Other

Cause:
User has selected PSTN call method but its profile cannot be found for the user to read the contact number.

Action:
Ensure that the user profile exists in the system.

WCS-04905
Cannot process call request : Contact information for user {0} not found

Category:
Other

Cause:
User has selected PSTN call method but has not supplied the correct ldap attribute to read the contact information.

Action:
Ensure that correct ldap attribute has been supplied in connection/adf-config and its value has been set in the profile.

WCS-04906
Cannot process call request : Incorrect call method supplied

Category:
Other

Cause:
User has supplied an incorrect call method.

Action:
Ensure that correct call method is supplied. Refer to the documentation to find the supported call methods.

WCS-04907
Cannot process call request : Call domain not specified in connection.

Category:
Other

Cause:
User has selected PSTN call method but has not supplied the call.domain property.

Action:
Ensure that correct call.domain has been supplied in connection/adf-config.

WCS-04908
Cannot process call request : User name is missing or not provided.

Category:
Other

Cause:
User name is missing or it has not been provided.

Action:
Ensure that correct user name is provided, contact administrator.

WCS-05001
Cannot retrieve the metadata for a portal

Category:
Other

Cause:
Unable to fetch the portal metadata due to an internal error.

Action:
Contact Oracle Support Services.

WCS-05002
An error occurred while trying to get the ScopeAPI implementation for the service {0}.

Category:
Other

Cause:
Service {0} does not support provisioning.

Action:
Contact Oracle Support Services.

WCS-05003
The service object passed to the wrapper is null.

Category:
Other

Cause:
A null service object was retrieved from the service registry.

Action:
Contact Oracle Support Services.

WCS-05004
A portal template named {0} already exists.

Category:
Other

Cause:
Name specified for the portal template was not unique. A template with the same name already exists.

Action:
Provide a unique name for the portal template.

WCS-05005
Cannot create portal template

Category:
Other

Cause:
No name was provided for the portal template.

Action:
Provide a unique name for the portal template.

WCS-05006
Unable to retrieve information about {0}.

Category:
Other

Cause:
No portal template was found with the name specified.

Action:
Provide the name of an existing portal template.

WCS-05007
The reference to the portal template metadata {0} is invalid.

Category:
Other

Cause:
No portal template was found with the name specified.

Action:
Provide the name of an existing portal template.

WCS-05008
Unable to get mutable metadata for the portal template {0}

Category:
Other

Cause:
Some portion of the portal template metadata has already been modified.

Action:
Contact Oracle Support Services.

WCS-05009
Metadata for the portal template {0} is invalid.

Category:
Other

Cause:
MDS reported a metadata validation error.

Action:
Contact Oracle Support Services.

WCS-05010
An error occurred reading or writing metadata of portal template {0}.

Category:
Other

Cause:
MDS reported an IO error.

Action:
Contact Oracle Support Services.

WCS-05011
The commit operation failed due to a concurrent metadata change for portal template {0}.

Category:
Other

Cause:
MDS reported a concurrent metadata change error.

Action:
Contact Oracle Support Services.

WCS-05012
Couldn''t retrieve the portal members email ids for {0} due to {1}.

Category:
Other

Cause:

Action:

WCS-05013
Unable to execute portal related operation on {0}

Category:
Other

Cause:
Either the metadata did not exist, an invalid metadata reference was used or an attempt was made to get mutable metadata that has already been changed.

Action:
Contact Oracle Support Services.

WCS-05014
Unable to get metadata for portal {0}.

Category:
Other

Cause:
Either the metadata did not exist, an invalid metadata reference was used or an attempt was made to get mutable metadata that has already been changed.

Action:
Contact Oracle Support Services.

WCS-05015
Cannot create metadata for portal {0}

Category:
Other

Cause:
Metadata for the specified portal already exists.

Action:
Provide a different name.

WCS-05018
The reference to the metadata of portal {0} is invalid.

Category:
Other

Cause:
The metadata reference was invalid.

Action:
Contact Oracle Support Services.

WCS-05019
Unable to get mutable metadata for portal {0}

Category:
Other

Cause:
Some portion of the portal metadata has already been modified.

Action:
Contact Oracle Support Services.

WCS-05020
Metadata of portal {0} is invalid.

Category:
Other

Cause:
MDS reported a metadata validation error.

Action:
Contact Oracle Support Services.

WCS-05021
An error occurred reading or writing metadata of portal {0}.

Category:
Other

Cause:
MDS reported an IO error.

Action:
Contact Oracle Support Services.

WCS-05022
The commit operation failed due to a concurrent metadata change for portal {0}.

Category:
Other

Cause:
MDS reported a concurrent metadata change error.

Action:
Contact Oracle Support Services.

WCS-05023
Cannot retrieve a list of members for the current portal.

Category:
Other

Cause:
An error occurred trying to access the specified portal.

Action:
Contact Oracle Support Services.

WCS-05025
Could not create portal {0} from portal template {1}.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Administrator.

WCS-05026
Could not create portal template {1} from portal {0}.

Category:
Other

Cause:
Either the specified portal template already exists or the name was invalid.

Action:
Provide a valid,unique name for the portal template.

WCS-05027
Unable to get preference metadata for portal {0}

Category:
Other

Cause:
Either the metadata does not exist, an invalid metadata reference was used or an attempt was made to get mutable metadata that has changed.

Action:
Contact Oracle Support Services.

WCS-05035
Unexpected error in renaming portal from {0} to {1}. Contact administrator or try again after some time.

Category:
Other

Cause:
An invalid character was found in the name.

Action:
Remove the invalid character(s) from the name and try again.

WCS-05036
A portal with the URL {0} already exists.

Category:
Other

Cause:
A portal with the specified URL exists.

Action:
Specify a unique name for the portal.

WCS-05037
The portal template name contains an invalid character {0}.

Category:
Other

Cause:
An invalid character was found in the portal template name.

Action:
Remove the invalid character(s) from the portal template name and try again.

WCS-05038
A portal template named {0} already exists.

Category:
Other

Cause:
A portal template with the specified name already exists.

Action:
Specify a unique name for the portal template.

WCS-05039
An error occurred attempting to save this portal as a portal template.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05040
The portal name contains one or more blank space characters.

Category:
Other

Cause:
A blank was found in the portal name. Blank spaces are not allowed.

Action:
Remove all blank spaces from the portal name and try again.

WCS-05041
The portal template name contains one or more blank space characters.

Category:
Other

Cause:
A blank space was found in the name of the portal template. Blank spaces are not allowed.

Action:
Remove all blank spaces from the portal template name and try again.

WCS-05042
Unable to get metadata {1} for portal {0}.

Category:
Other

Cause:
Either the metadata did not exist, an invalid metadata reference was used or an attempt was made to get mutable metadata that has already been changed.

Action:
Contact Oracle Support Services.

WCS-05043
A portal with title {0} already exists. While the portal may not be available to you, another portal has that title. Choose a different title for your portal.

Category:
Other

Cause:
A portal with the specified display name exists.

Action:
Specify a unique display name for the portal.

WCS-05047
Sending invitation to user(s) failed. The reason is : {0}.

Category:
Other

Cause:
Connection details for the BPEL server providing portal invitation services were not available.

Action:
Ask your administrator to configure a connection to the BPEL server providing portal invitation services.

WCS-05048
Unexpected error occurred while trying to invite user(s) to portal {0}

Category:
Other

Cause:
The BPEL server that provides the portal invitation service might have been down.

Action:
Ask your administrator to restart the BPEL server, and try again.

WCS-05058
Cannot create policy store metadata for portal {0}

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05059
Cannot save the changes

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05063
Cannot delete portal {0} due to unknown errors.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05065
Cannot not get the list of available services

Category:
Other

Cause:
No services were available in the service registry.

Action:
Contact Oracle Support Services.

WCS-05066
An error occurred while attempting to unsubscribe a user from portal {0}.

Category:
Other

Cause:
The BPEL server supporting portal unsubscription may be down

Action:
Ask your administrator to restart the BPEL server and try again.

WCS-05067
Unable to send unsubscription request to Portal Manager(s). The reason is : {0}.

Category:
Other

Cause:
Connection details for the BPEL server providing portal unsubscription services were not available.

Action:
Ask your administrator to configure a connection to the BPEL server providing portal unsubscription services.

WCS-05068
An error occurred attempting to unsubscribe user from portal {0}: {1}.

Category:
Other

Cause:
Connection details for the BPEL server providing portal unsubscription services were not available.

Action:
Ask your administrator to configure a connection to the BPEL server providing portal unsubscription services.

WCS-05069
Unable to send subscription notification to Portal Manager(s). The reason is : {0}.

Category:
Other

Cause:
The BPEL URL has not been configured yet.

Action:
Notify your administrator that the BPEL service supporting portal subscription is not configured

WCS-05070
An error occurred attempting to subscribe a user to portal{0}.

Category:
Other

Cause:
The BPEL server providing the portal subscription service may be down.

Action:
Ask your administrator to restart the BPEL server, and try again.

WCS-05071
An error occurred attempting to subscribe user to portal {0}: {1}.

Category:
Other

Cause:
The BPEL server providing the portal subscription service may be down.

Action:
Ask your administrator to restart the BPEL server, and try again.

WCS-05072
Error occurred while navigating to portal {0}.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-05073
Could not create portal with name {0}

Category:
Other

Cause:
The portal name provided could not be created.

Action:
Please contact Administrator.

WCS-05074
An error occurred attempting to access a page of the renamed portal.

Category:
Other

Cause:
The portal rename operation was not successful.

Action:
Contact Oracle Support Services.

WCS-05075
An error occurred attempting to rename a portal.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05077
Could not retrieve portal workflow configuration. Please contact administrator.

Category:
Other

Cause:
An error occurred attempting to retrieve the BPEL Several URL configured in connections.xml

Action:
Contact Oracle Support Services.

WCS-05078
Cannot delete workflow approval metadata from the portal

Category:
Other

Cause:

Action:

WCS-05079
Cannot get the security handler for portal template {0}

Category:
Other

Cause:
The policy store metadata was not available for portal template security initialization.

Action:
Contact Oracle Support Services.

WCS-05080
Cannot create the portal template {0}

Category:
Other

Cause:
The portal template was not created due to an error reported by the metadata store.

Action:
Contact Oracle Support Services.

WCS-05081
Unable to retrieve metadata object for portal {0}

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05082
Adding workflow approval metadata to the portal failed

Category:
Other

Cause:

Action:

WCS-05083
An error occurred attempting to rename portal {0} to {1}.

Category:
Other

Cause:
The portal rename operation was successful.

Action:
Contact Oracle Support Services.

WCS-05084
An unexpected error occurred attempting to delete portal {0}.

Category:
Other

Cause:
The portal delete operation was unsuccessful.

Action:
Contact Oracle Support Services.

WCS-05085
Portal name cannot be null

Category:
Other

Cause:
Portal name was blank.

Action:
Enter a valid alphanumeric name for the portal

WCS-05086
Portal name is a reserved keyword.

Category:
Other

Cause:
The portal name specified was a reserved keyword.

Action:
Specify a valid alphanumeric name for the portal which excludes the following reserved keywords: webcenter, pages, page, spaces, space, group, groups, space, spaces, webcenter space, webcenter spaces, webcenter Portal, WebCenter Portal, WebCenter Portal spaces, portal, webcenter administration, my spaces, admin, last, system.

WCS-05087
The portal name contains invalid characters. Only alphanumeric and space characters are allowed.

Category:
Other

Cause:
Portal name contained non-alphanumeric/space characters.

Action:
Specify a valid alphanumeric name for the portal that only contains a-z, A-Z, 0-9, _, or a space character

WCS-05088
Cannot delete the seeded portal template {0}

Category:
Other

Cause:
An attempt was made to delete a seeded portal template.

Action:
Do not try to delete a seeded portal template.

WCS-05089
Connection details for the BPEL server providing portal notification services are not available. Unable to send add or delete notifications to members of portal{0}

Category:
Other

Cause:
Connection details for the BPEL server providing portal invitation services were not available or configured incorrectly.

Action:
Ask your administrator to configure a connection to the BPEL server providing portal notification services.

WCS-05090
An error occurred attempting to send a notification to a member added to or deleted from portal {0}

Category:
Other

Cause:
An error occurred attempting to send a portal notification.

Action:
Contact Oracle Support.

WCS-05091
Connection details for the BPEL server providing notification services in WebCenter Portal not found.

Category:
Other

Cause:
Connection details for the BPEL server providing notification services in WebCenter Portal were not available.

Action:
Ask the administrator to configure a connection to the BPEL server providing notification services in WebCenter Portal.

WCS-05092
One of the arguments passed to API call {0} is null

Category:
Other

Cause:
A null argument was passed to an API call

Action:
Invoke the API with non-null arguments

WCS-05093
Portal template name cannot be null

Category:
Other

Cause:
No name was specified for the portal template.

Action:
Specify a valid alphanumeric name for portal template.

WCS-05094
Portal template name is a reserved keyword.

Category:
Other

Cause:
The template name specified was a reserved keyword.

Action:
Specify a valid alphanumeric name for the template which excludes the following reserved keywords: admin, builder, group, groups, home, last, page, pages, my portals, my spaces, portal, portals, spaces, space, system, webcenter, webcenter administration, webcenter portal, webcenter portals, webcenter space, webcenter spaces.

WCS-05095
Template name contains invalid characters. Only alphanumeric and space characters are allowed.

Category:
Other

Cause:
Template name contains non-alphanumeric or space characters

Action:
Specify a valid alphanumeric name for the template that only contains:a-z, A-Z, 0-9, _, or a space character

WCS-05096
A portal template with name {0} already exists.

Category:
Other

Cause:
A portal template with the specified name exists.

Action:
Specify a unique name.

WCS-05097
Cannot upload portal icon

Category:
Other

Cause:
An error occurred while attempting to upload the file to WebCenter Portal

Action:
Try again or contact Oracle Support Services

WCS-05098
Cannot upload a portal logo

Category:
Other

Cause:
An error occurred attempting to upload the file to WebCenter Portal

Action:
Try again or contact Oracle Support Services

WCS-05099
Unable to set lock on portal {0}

Category:
Other

Cause:
A lock could not be acquired for this portal.

Action:
Try again later.

WCS-05100
Unable to execute operation on portal {0}

Category:
Other

Cause:
Portal {0} was locked by some other operation.

Action:
Wait for the first operation to complete and try again.

WCS-05101
Unable to execute portal operation

Category:
Other

Cause:
The portal was locked by some other operation.

Action:
Wait for the first operation to complete and try again.

WCS-05102
Error creating portal {0} from portal template {1}

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05103
Errors while renaming portal {0}

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05104
Unexpected error while trying to request change membership to portal {0}

Category:
Other

Cause:
The BPEL server might have been down.

Action:
Ensure BPEL server is up and retry. Contact the portal manager for assistance.

WCS-05105
Unexpected error while trying to send notification to user {0}

Category:
Other

Cause:
The BPEL server might have been down.

Action:
Ensure BPEL server is up and retry. Contact the portal manager for assistance.

WCS-05106
Unexpected error creating region in cache

Category:
Other

Cause:
An attempt to create a region in the JOC (Java Object Cache) failed.

Action:
Ensure that the JOC configuration is correct.

WCS-05107
Unexpected error getting object {0} from region {1} in cache

Category:
Other

Cause:
An attempt to retrieve an object from the cache failed.

Action:
Ensure that the JOC configuration is correct.

WCS-05108
Search {0} for portal returned more than {2} results.

Category:
Other

Cause:
Search matched {1} results for portal template. The maximum number of result records allowed for this report is {1}.

Action:
Restrict your query further, or use a different query.

WCS-05109
Portal operation resulted in unexpected exception.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05111
Creating template resulted in unexpected exception.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05112
Fetching portal member count resulted in unexpected exception.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05113
An error occurred while trying to provision the service {0}. The service did not get provisioned.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05114
An error occurred while trying to unprovision the service {0}. The service did not get unprovisioned.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05115
An error occurred while trying to determine the selected service.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Reload the browser page, and if problem persists, contact the administrator.

WCS-05116
An error occurred while trying to process the service that was selected.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Reload the browser page, and if problem persists, contact the administrator.

WCS-05117
An error occurred while trying to load the configuration screen for the selected service.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Reload the browser page, and if problem persists, contact the administrator.

WCS-05118
Failed to delete portal {0} security metadata

Category:
Other

Cause:
Deletion of portal security metadata failed

Action:
An unexpected error occurred while trying to deleting portal {0}. Please contact administrator for assistance.

WCS-05119
An unexpected error occurred while trying to provision/unprovision services.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05120
An unexpected error occurred while trying to save the configuration for the service {0}.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05121
An unexpected error occurred while trying to upload an image for portal {0}.

Category:
Other

Cause:
An unexpected error occurred during image upload.

Action:
Contact the administrator.

WCS-05122
There was an error while fetching the GUID for portal {0}.

Category:
Other

Cause:
An unexpected error occurred while fetching the GUID for portal {0}.

Action:
Contact the administrator.

WCS-05123
Metadata Not Found Exception occurred while fetching the service config metadata for a portal {0}.

Category:
Other

Cause:
An unexpected error occurred while fetching the service config metadata for portal {0}

Action:
Contact the administrator.

WCS-05124
An exception occurred while fetching the Portal Manager for portal {0}.

Category:
Other

Cause:
An unexpected error occurred while fetching the Portal Manager for portal {0}.

Action:
Contact the administrator.

WCS-05125
An exception occurred while fetching the Portal Manager for portal {0}.

Category:
Other

Cause:
An unexpected error occurred while fetching the Portal Manager for portal {0}.

Action:
Contact the administrator.

WCS-05126
An exception occurred while fetching the GUID for portal {0}.

Category:
Other

Cause:
An unexpected error occurred while fetching the GUID for portal {0}.

Action:
Contact the administrator.

WCS-05127
An exception occurred while fetching the contacts list for portal {0}.

Category:
Other

Cause:
An unexpected error occurred fetching the contacts list for portal {0}.

Action:
Contact the administrator.

WCS-05128
An exception occurred while fetching the GUID for portal {0}.

Category:
Other

Cause:
An unexpected error occurred while fetching the GUID for portal {0}.

Action:
Contact the administrator.

WCS-05129
Error occurred while launching the delete role confirmation.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05130
Error occurred while launching add/invite members table.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05131
Error occurred while getting the message for inviting non-members.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05132
Error occurred while performing operations on roles.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05133
Error occurred while adding custom attributes name={0} and value={1}.

Category:
Other

Cause:
An unexpected error occurred while adding the custom attributes.

Action:
Contact the administrator.

WCS-05134
Error occurred while deleting the name={0} custom attribute

Category:
Other

Cause:
An unexpected error occurred while deleting the custom attribute.

Action:
Contact the administrator.

WCS-05135
Error occurred while editing the custom attribute name={0} and value={1}.

Category:
Other

Cause:
An unexpected error occurred while editing the custom attribute.

Action:
Contact the administrator.

WCS-05136
Error occurred while fetching the custom attributes for portal {0}.

Category:
Other

Cause:
An unexpected error occurred while fetching the custom attribute.

Action:
Contact the administrator.

WCS-05137
No Such Attribute exists.

Category:
Other

Cause:
Unable to find the custom attributes

Action:
Contact the administrator.

WCS-05138
Unexpected error in getting the list of portals. You can try again later or contact Administrator.

Category:
Other

Cause:
Unexpected error in getting portals.

Action:
Please contact administrator.

WCS-05139
Unexpected error in retrieving portal {0}.

Category:
Other

Cause:
Unexpected error in retrieving the portal.

Action:
Contact Administrator.

WCS-05140
Unexpected error while rolling back the service {0}

Category:
Other

Cause:
Error in rolling back the service.

Action:
Contact Administrator.

WCS-05141
Unknown errors creating portal. Please contact Administrator.

Category:
Other

Cause:
Post creating the portal, there were errors.

Action:
Contact administrator.

WCS-05142
Portal was created successfully but refreshing the portal list failed. You may try to refresh the portal list manually.

Category:
Other

Cause:
List refresh failed after creating portal.

Action:
Manually refresh the portal list.

WCS-05143
Errors were encountered in creating portal. The main error is - {0}. You may want to delete the current portal if it is visible in your lists. Contact the administrator if the problem persists.

Category:
Other

Cause:
Errors were seen in post-processing the create portal.

Action:
Contact Administrator.

WCS-05144
Errors were encountered while creating the portal. The main error is - {0}. Rollback of the creation also failed. You may want to clean the current portal if it is visible in your lists. You may want to try to create the portal again later or contact the administrator.

Category:
Other

Cause:
Error in post-processing the portal.

Action:
Contact administrator.

WCS-05145
Portal created with the following warning(s) : {0}

Category:
Other

Cause:
Portal was created with warnings.

Action:
Contact Administrator.

WCS-05146
Unexpected errors in deleting the portal. Contact Administrator.

Category:
Other

Cause:
Unexpected error in deleting the portal.

Action:
Contact administrator.

WCS-05147
Deletion of the portal resulted in errors. The main error is - {0}. You may want to try deleting the portal again later. If the error persists, contact the administrator.

Category:
Other

Cause:
Delete of the portal resulted in error.

Action:
Contact Administrator.

WCS-05148
Deletion of portal resulted in errors. The main error is - {0}. Rollback of the deletion failed as well. You may want to try deleting the portal again later. If the error persists, contact the administrator.

Category:
Other

Cause:
Delete of the portal resulted in error.

Action:
Contact Administrator

WCS-05149
Portal was deleted successfully but refreshing the portal list failed. You may try to refresh the portal list manually.

Category:
Other

Cause:
List refresh failed after deleting portal.

Action:
You can refresh the portal list manually.

WCS-05150
Unexpected errors in renaming the portal. Contact Administrator.

Category:
Other

Cause:
Unknown errors in renaming the portal.

Action:
Contact Administrator.

WCS-05151
Rename of the portal resulted in errors. The main error is - {0}. You may want to try to rename the portal again later. If the error persists, contact the administrator.

Category:
Other

Cause:
Rename of the portal resulted in error.

Action:
Contact Administrator.

WCS-05152
Rename of the portal resulted in errors. The main error is - {0}. Rollback of renaming also failed. You may want to try to rename the portal again later or contact the administrator.

Category:
Other

Cause:
Portal was renamed but there were errors in processing.

Action:
Contact administrator.

WCS-05153
Portal was renamed successfully but refreshing the portal list failed. You may try to refresh the portal list manually.

Category:
Other

Cause:
Refreshing the list after renaming the portal failed.

Action:
Manually refresh the list of portals.

WCS-05154
Portal was renamed with warnings. These are some of the warnings - {0}.

Category:
Other

Cause:
Portal was renamed with warnings.

Action:
Contact Administrator.

WCS-05155
Unexpected error in retrieving the portal list.

Category:
Other

Cause:
Unexpected error in retrieving the portal list.

Action:
Try again after some time. If problem persist, contact administrator.

WCS-05156
Unexpected error while provisioning some optional services in the portal. You may want to provision them again by going to portal Administration.

Category:
Other

Cause:
Unexpected error while provisioning some optional services in the portal.

Action:
Contact Administrator.

WCS-05157
Provisioning some optional services {0} in the portal did not go through successfully. You may want to provision them again by going to portal Administration.

Category:
Other

Cause:
Provisioning some optional services in the portal did not go through successfully.

Action:
Contact Administrator.

WCS-05158
Unexpected error while unprovisioning the services.

Category:
Other

Cause:
Unexpected error in unprovisioning the services.

Action:
Contact administrator.

WCS-05159
Portal was deleted with warnings. These are some of the warnings - {0}.

Category:
Other

Cause:
Portal was renamed with warnings.

Action:
Contact Administrator.

WCS-05160
Unexpected errors while granting user access on new portal {0}. Please contact Administrator.

Category:
Other

Cause:
Unexpected errors while granting access on new portal {0}

Action:
Contact Administrator.

WCS-05161
Unexpected errors while removing access on new portal {0}. Please contact Administrator.

Category:
Other

Cause:
Unexpected errors while removing access on new portal {0}

Action:
Contact Administrator.

WCS-05162
Unknown error while removing access for portal {0}

Category:
Other

Cause:
Unexpected errors while removing access on portal {0}

Action:
Contact Administrator.

WCS-05163
Unknown error while mapping access for the new portal {0}

Category:
Other

Cause:
Unexpected errors while mapping access on portal {0}

Action:
Contact Administrator.

WCS-05164
Unexpected errors in provisioning services for new portal {0}

Category:
Other

Cause:
Unexpected errors in provisioning services for new portal {0}

Action:
Contact Administrator.

WCS-05165
Unknown error while reprovisioning services since delete failed for portal {0}

Category:
Other

Cause:
Unexpected errors while reprovisioning services on portal {0}

Action:
Contact Administrator.

WCS-05166
Unknown error while creating metadata for new template {0}

Category:
Other

Cause:
Unexpected errors while copying metadata from portal {0} to template {1}

Action:
Contact Administrator.

WCS-05167
Unknown error in creating metadata for the new portal {0}

Category:
Other

Cause:
Unexpected errors while creating metadata for portal {0}

Action:
Contact Administrator.

WCS-05168
Unknown error in renaming the portal.

Category:
Other

Cause:
Unexpected errors in renaming the portal.

Action:
Contact Administrator.

WCS-05169
Unknown error in renaming services from portal {0} to portal {1}.

Category:
Other

Cause:
Unexpected errors in renaming the services.

Action:
Contact Administrator.

WCS-05170
Updates or deletes are being performed on portal {0} by another Portal Manager. Please try again after some time.

Category:
Other

Cause:
Portal {0} is already being deleted.

Action:
Contact Administrator.

WCS-05171
Error occurred while trying to determine if service {0} is provisioned in the current portal.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05172
The role {0} does not exist and hence could not be assigned to the user {1}.

Category:
Other

Cause:
Role {0} may have already been deleted .

Action:
Contact the administrator.

WCS-05173
Error occurred while trying to modify the role for user {0}.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05174
Error occurred while accessing footer information.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05175
Portal {0} already exists.

Category:
Other

Cause:
Name specified for the portal was not unique. A portal with the same name already exists.

Action:
Provide a unique name for the portal.

WCS-05176
Portal name must contain at least one alphanumeric character

Category:
Other

Cause:
Portal name did not contain any alphanumeric characters

Action:
Provide at least one alphanumeric character for portal name.

WCS-05177
Unable to perform the operation on the selected portal(s) due to unknown errors

Category:
Other

Cause:
Selection of portal(s) failed

Action:
Contact the administrator.

WCS-05178
Failed to refresh the portal list due to unknown errors

Category:
Other

Cause:
Unknown error occurred while trying to refresh the portal list

Action:
Contact the administrator.

WCS-05179
Unable to perform the operation on the selected portal template(s) due to unavoidable errors

Category:
Other

Cause:
Selection of portal template(s) failed

Action:
Contact the administrator.

WCS-05180
An error occurred while trying to delete the portal template(s).

Category:
Other

Cause:
Selection of portal template(s) failed

Action:
Contact the administrator.

WCS-05181
Error while creating portal

Category:
Other

Cause:
Error occurred during portal creation

Action:
Contact the administrator.

WCS-05182
Error in closing the Create Portal dialog.

Category:
Other

Cause:
Error occurred while closing the Create Portal dialog

Action:
Contact the administrator.

WCS-05183
Another user is modifying the settings. Please try after some time.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05184
Unable to delete selected portal(s).

Category:
Other

Cause:
Selection of portal(s) failed

Action:
Contact the administrator.

WCS-05185
Unable to export selected portal(s) due to unknown errors

Category:
Other

Cause:
Selection of portal(s) failed

Action:
Contact the administrator.

WCS-05186
Error occurred while checking existing status of portal {0}.

Category:
Other

Cause:
An unexpected error occurred while checking existing status of the portal.

Action:
Contact the administrator.

WCS-05187
Error occurred while retrieving portal {0} creation date

Category:
Other

Cause:
An unexpected error occurred while retrieving the portal creation date.

Action:
Contact the administrator.

WCS-05188
Error occurred while retrieving portal {0} status changed date.

Category:
Other

Cause:
An unexpected error occurred while retrieving the portal status changed date.

Action:
Contact the administrator.

WCS-05189
Failed to validate the name/display name

Category:
Other

Cause:
Failed to validate the name/display name

Action:
Contact the administrator.

WCS-05190
An error occurred in post-processing the invite for {0} in portal {1}. Please contact Administrator.

Category:
Other

Cause:
Unable to cleanup invited status metadata

Action:
Please contact Administrator for assistance.

WCS-05191
Unexpected error occurred while saving the portal changes.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05192
Unexpected error occurred while making portal public.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05193
Unexpected error retrieving data for the Portal Switcher.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05194
Portal template {0} based on portal {1} created successfully with the errors.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05195
Portal template {0} deletion failed due to concurrent operation performed on the same resource by some other user.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05197
Portal mail ID is not available because the Mail service is not configured.

Category:
Other

Cause:
Portal mail ID is not available because the Mail service is not configured.

Action:
Contact the administrator to configure the Mail service.

WCS-05198
Failed to initialize cache for portal template {0}.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05200
Failed to update cache for portal template {0}.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05201
Unknown error occurred while processing the templates.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05202
User was added but could not be notified due to some errors.

Category:
Other

Cause:
The BPEL server may be down.

Action:
Ensure BPEL server is up and retry.

WCS-05203
Template name must contain at least one alphanumeric character

Category:
Other

Cause:
Template name did not contain any alphanumeric characters

Action:
Provide at least one alphanumeric character for template name.

WCS-05204
Portal display name cannot be null.

Category:
Other

Cause:
Portal display name was blank.

Action:
Enter a valid alphanumeric name for the portal display name

WCS-05205
Portal display name is a reserved keyword. One of: {0}

Category:
Other

Cause:
The portal display name specified was a reserved keyword

Action:
Specify a valid alphanumeric name for the portal display name which excludes the following reserved keywords: admin, builder, group, groups, home, last, page, pages, my portals, my spaces, portal, portals, spaces, space, system, webcenter, webcenter administration, webcenter portal,webcenter portals, webcenter space, webcenter spaces.

WCS-05206
The portal name contains invalid characters.

Category:
Other

Cause:
Portal display name contained non-alphanumeric/space characters.

Action:
Specify a valid alphanumeric name for the portal display name that only contains a-z, A-Z, 0-9, _, or a space character

WCS-05207
The portal name must contain at least one letter or number.

Category:
Other

Cause:
Portal display name did not contain any alphanumeric characters

Action:
Provide at least one alphanumeric character for portal display name.

WCS-05208
Select at least one portal to change state/status of portal.

Category:
Other

Cause:
No portal has been selected or changing the state.

Action:
Select at least one portal.

WCS-05209
There are no templates available for creating the portal(s). You should refresh the list of templates by going to the Portal Templates page or create new templates or publish available templates if any to continue creating portal(s). If the problem persists, contact system administrator

Category:
Other

Cause:
No templates available for creating portal.

Action:
Create new templates or publish existing templates if any.

WCS-05210
Unknown error occurred while initiating creation of a portal.

Category:
Other

Cause:
Unable to launch the Create Portal dialog.

Action:
Contact system administrator.

WCS-05211
Unknown error occurred while retrieving the list of templates.

Category:
Other

Cause:
Unknown error occurred while retrieving the list of templates.

Action:
Contact system administrator.

WCS-05212
User {0} not authorized to perform the operation {1}:{2}

Category:
Other

Cause:
User {0} not authorized to perform the operation {1}:{2}

Action:
User {0} not authorized to perform the operation {1}:{2}

WCS-05213
Unexpected Error occurred while performing the method {0}. Contact system administrator.

Category:
Other

Cause:
Unexpected Error occurred while performing the method {0}.

Action:
Contact system administrator.

WCS-05214
Unable to retrieve information about {0} as another user is modifying the {0}. Please try again after some time.

Category:
Other

Cause:
Cannot retrieve metadata for portal {0} as another user is modifying the settings. Please try after some time.

Action:
Contact Oracle Support Services.

WCS-05215
User(s) added successfully, but sending notification to the user(s) failed

Category:
Other

Cause:
The BPEL server may be down.

Action:
Ensure BPEL server is up and retry.

WCS-05216
User was removed successfully, but sending notification to the user failed

Category:
Other

Cause:
The BPEL server may be down.

Action:
Ensure BPEL server is up and retry.

WCS-05217
User role was modified successfully, but sending notification to the user failed

Category:
Other

Cause:
The BPEL server may be down.

Action:
Ensure BPEL server is up and retry.

WCS-05218
Unknown error occurred while navigating to portal {0}.

Category:
Other

Cause:
Unable to navigate to the portal.

Action:
Contact system administrator.

WCS-05219
Try accessing the portal from the Portal Switcher menu or the Portal page if the portal creation resulted in warnings. If the portal is not listed, refresh the list. If the portal is still not visible, report the error to your administrator. If the portal creation resulted in error, try deleting the portal if it is visible or else request the administrator to delete the portal

Category:
Other

Cause:
You can try accessing the portal from the Portal Switcher menu or the Portal page. If the portal is not listed, try refreshing the listing on the Portal page.

Action:
Contact system administrator.

WCS-05220
Deletion or Rename is being performed on portal {0} by another Portal Manager. Refresh the list of portals and try again after some time.

Category:
Other

Cause:
Portal {0} is already being deleted or renamed.

Action:
Contact Administrator.

WCS-05221
An unexpected error occurred while trying to delete portal template. Try again after some time. If the problem persists, contact administrator.

Category:
Other

Cause:
An unexpected error occurred while trying to delete portal template.

Action:
Contact system administrator.

WCS-05222
Some optional services in the portal could not be provisioned as they were disabled. You may want to provision them again by going to portal Administration.

Category:
Other

Cause:
Unexpected error while provisioning some optional services in the portal.

Action:
Contact Administrator and look in the logs for information about the specific service that has been disabled.

WCS-05223
Admin Role does not exist in the policy store for portal {0}, so creating it

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-05224
Unexpected error occurred while revoking portal public status.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05225
Cannot retrieve the portal distribution list for {0} due to {1}.

Category:
Other

Cause:

Action:

WCS-05226
Cannot retrieve the portal managers list for {0} due to {1}.

Category:
Other

Cause:

Action:

WCS-05227
Cannot retrieve the Webcenter Portal administrators list due to {1}.

Category:
Other

Cause:

Action:

WCS-05228
Unable to send change membership notification. The reason is : {0}.

Category:
Other

Cause:
The BPEL URL has not been configured yet.

Action:
Notify your administrator that the BPEL service supporting portal subscription is not configured

WCS-05229
Cannot retrieve portal workflow configuration. Please contact your administrator.

Category:
Other

Cause:
The BPEL URL has not been configured yet.

Action:
Notify your administrator that the BPEL service supporting portal subscription is not configured

WCS-05230
An error occurred while searching invited user {0} in portal {1}. Contact your administrator.

Category:
Other

Cause:
Unable to search invited status metadata

Action:
Contact your administrator for assistance.

WCS-05231
Cannot retrieve user {0} email ID in portal {1} due to {2}

Category:
Other

Cause:
Failed to retrieve email id due to {2}

Action:
Contact your administrator for assistance.

WCS-05232
Template publishing role does not exist in the policy store for portal {0}, so creating it

Category:
Other

Cause:
Copy of the role failed, now trying to sanitize the portal security data

Action:
Contact Oracle Support Services.

WCS-05233
Sanitizing template {0} failed unable to copy the publish data

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-05234
WebCenter Portal is not configured with BPEL server information.

Category:
Other

Cause:
BPEL server is not configured.

Action:
Contact your administrator for assistance.

WCS-05235
WebCenter Portal is not properly configured with the required BPEL server information.

Category:
Other

Cause:
BPEL server information is not correct.

Action:
Contact your administrator for assistance.

WCS-05236
BPEL server is either down or not properly configured.

Category:
Other

Cause:
Either the BPEL server is down or the portal workflows are not configured properly

Action:
Contact your administrator for assistance.

WCS-05237
Unexpected error occurred rebuilding the user portals list.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05238
Unexpected error occurred rebuilding the public portals list.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05239
Unable to retrieve portal tags.

Category:
Other

Cause:
An error occurred while trying to retrieve the tags for portal.

Action:
Please contact Administrator for assistance.

WCS-05240
Unable to create portal tags.

Category:
Other

Cause:
An error occurred while trying to create the tags for portal.

Action:
Please contact Administrator for assistance.

WCS-05241
Error occurred while getting portal activity streaming preferences.

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-05242
Error occurred while fetching the portal members information.

Category:
Other

Cause:
Error occurred while fetching the portal members information.

Action:
Contact Oracle Support Services.

WCS-05243
Unexpected error deriving {0} list.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact system administrator.

WCS-05244
The member's current role is selected. If you want to change this member's role, choose another role from the list.

Category:
Other

Cause:
The new role is same as the old role.

Action:
Select new role.

WCS-05246
Unexpected error persisting portal information to tables

Category:
Other

Cause:
Error saving portal information to the database

Action:
Contact Oracle Support Services.

WCS-05247
Unable to retrieve mail ID for the portal.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05248
Unable to find security policy store metadata while creating portal template {0}

Category:
Other

Cause:
An error was detected in the application's configuration.

Action:
Contact Oracle Support Services.

WCS-05249
Unexpected error occurred fetching ratings table from repository.

Category:
Other

Cause:
An unexpected error occurred fetching the bulk ratings table from the repository.

Action:
Contact the administrator.

WCS-05250
Unable to delete portal {0} as either it is being exported or imported. Please refresh the list portals list and try again later.

Category:
Other

Cause:
Attempt to delete portal {0} when the portal is being exported/imported.

Action:
Try delete after sometime. Contact the administrator if the problem persists.

WCS-05251
Unable to delete the portal template {0} as either it is being exported or imported. Please refresh the portal templates list and try again later.

Category:
Other

Cause:
Attempt to delete portal template {0} when the portal is being exported/imported.

Action:
Try delete after sometime. Contact the administrator if the problem persists.

WCS-05252
Unexpected error in getting information from users table

Category:
Other

Cause:
Error in getting information from the database

Action:
Contact Oracle Support Services.

WCS-05253
Role {1} of a user {0} is changed successfully to Role {2}, with failures in some of the services {3}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05254
Unexpected error occurred while refreshing the portal cache

Category:
Other

Cause:
Unexpected error occurred while refreshing the portal cache

Action:
Contact Oracle Support Services.

WCS-05255
Unexpected error occurred while cleaning up some of the permissions

Category:
Other

Cause:
Failed to clean up the policies post portal creation due to unexpected error

Action:
Contact Oracle Support Services.

WCS-05256
Error while deleting security metadata for portal {0}.

Category:
Other

Cause:
An unexpected error occurred while deleting security metadata for portal. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-05267
Error while deleting security metadata for portal template {0}.

Category:
Other

Cause:
An unexpected error occurred while deleting security metadata for portal template. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-05268
Error occurred while fetching the portal data.

Category:
Other

Cause:
Error occurred while fetching the portal data.

Action:
Contact Administrator.

WCS-05269
Error occurred while fetching the portal template data.

Category:
Other

Cause:
Error occurred while fetching the portal template data.

Action:
Contact Administrator.

WCS-05270
You can add only a total of {0} items including subportals to the selected set. Remove items from selected set and try to add again.

Category:
Other

Cause:
Limit of selected set exceeded.

Action:
Remove items from selected set and add again.

WCS-05271
Please select one or more row to add.

Category:
Other

Cause:
No rows selected to add.

Action:
Select one or more rows and add again.

WCS-05272
Unexpected errors while granting user access on new portal template {0}. Please contact Administrator.

Category:
Other

Cause:
Unexpected errors while granting access on new group template : {0}

Action:
Contact Administrator.

WCS-05273
Unknown error in removing access for the portal template {0}

Category:
Other

Cause:
Unexpected errors while removing access on portal template {0}

Action:
Contact Administrator.

WCS-05274
Unable to find the security management lock for template {0}

Category:
Other

Cause:
Unable to find the security management lock for template {0}

Action:
Contact Administrator.

WCS-05275
Unexpected errors in provisioning services for new portal template {0}

Category:
Other

Cause:
Unexpected errors in provisioning services for new portal template {0}

Action:
Contact Administrator.

WCS-05276
Unknown error in reprovisioning services since delete failed for portal template {0}

Category:
Other

Cause:
Unexpected errors while reprovisioning services on portal template {0}

Action:
Contact Administrator.

WCS-05277
Unknown error in mapping access for the new portal template {0}

Category:
Other

Cause:
Unexpected errors while mapping access on portal template {0}

Action:
Contact Administrator.

WCS-05278
Portal template {0} already exists.

Category:
Other

Cause:
Name specified for the portal template was not unique. A portal template with the same name already exists.

Action:
Provide a unique name for the portal template.

WCS-05279
Unexpected error while rolling back the template during {0}

Category:
Other

Cause:
Error in rolling back the plugin.

Action:
Contact Administrator.

WCS-05280
Creation of portal template resulted in error. Rollback of the create template failed as well. The main error is - {0}. You may delete the template if it is available in the list as this template is in unusable state.

Category:
Other

Cause:
Error in rolling back the plugin.

Action:
Try deleting this template if it is available on the Portale Templates page.

WCS-05281
Rollback of portal template metadata also resulted in error. The main error is - {0}. Try deleting the template from the Portal Templates page if it is available as this template is in unusable state.

Category:
Other

Cause:
Error in deleting the template metadata.

Action:
Try deleting this template if it is available on the Portal Templates page.

WCS-05282
Unexpected errors in deleting the portal template. Contact Administrator.

Category:
Other

Cause:
Unexpected error in deleting the portal template.

Action:
Contact Administrator.

WCS-05283
Deletion of the portal template resulted in errors. The main error is - {0}. You may want to try again later. If the error persists, contact the administrator.

Category:
Other

Cause:
Delete of the portal template resulted in error.

Action:
Contact Administrator.

WCS-05284
Deletion of portal template resulted in errors. Rollback of the deletion failed as well. The main error is -{0}. You may want to try again later. If the error persists, contact the administrator.

Category:
Other

Cause:
Delete of the portal template resulted in error.

Action:
Contact Administrator

WCS-05285
Portal template was deleted successfully but refreshing the portal template list failed. You may try to refresh the portal template list manually.

Category:
Other

Cause:
List refresh failed after deleting portal template.

Action:
You can refresh the portal template list manually.

WCS-05286
Updates or deletes are being performed on portal template {0} by another Portal Manager. Please try again after some time.

Category:
Other

Cause:
Portal template {0} is already being deleted.

Action:
Contact Administrator.

WCS-05287
Unexpected errors occurred while creating template {0}.

Category:
Other

Cause:
Unexpected errors occurred while creating template.

Action:
Contact Administrator.

WCS-05288
Creation of template resulted in errors. The main error is - {0}. Try again after some time or contact administrator

Category:
Other

Cause:
Template creation resulted in errors.

Action:
Contact Administrator.

WCS-05289
Unexpected error occurred while executing pre portal template creation due to {0}.

Category:
Other

Cause:
Unexpected error occurred while executing pre portal template creation due to {0}.

Action:
Contact Administrator.

WCS-05290
Base portal name cannot be null

Category:
Other

Cause:
Base portal name cannot be null

Action:
Enter a value for base portal.

WCS-05291
Error occurred while executing custom pre portal creation code due to {0}.

Category:
Other

Cause:
Error occurred while executing custom pre portal creation due to {0}.

Action:
Contact Administrator.

WCS-05292
Error occurred while executing custom post portal creation code due to {0}.

Category:
Other

Cause:
Error occurred while executing custom post portal creation due to {0}.

Action:
Contact Administrator.

WCS-05293
Error occurred while executing custom pre portal deletion code due to {0}.

Category:
Other

Cause:
Error occurred while executing custom pre portal deletion due to {0}.

Action:
Contact Administrator.

WCS-05294
Error occurred while executing custom post portal deletion code due to {0}.

Category:
Other

Cause:
Error occurred while executing custom post portal deletion due to {0}.

Action:
Contact Administrator.

WCS-05295
Error occurred while executing custom pre portal rename code due to {0}.

Category:
Other

Cause:
Error occurred while executing custom pre portal rename due to {0}.

Action:
Contact Administrator.

WCS-05296
Error occurred while executing custom post portal rename code due to {0}.

Category:
Other

Cause:
Error occurred while executing custom post portal rename due to {0}.

Action:
Contact Administrator.

WCS-05297
Error occurred while executing custom pre portal template creation code due to {0}.

Category:
Other

Cause:
Error occurred while executing custom pre portal template creation due to {0}.

Action:
Contact Administrator.

WCS-05298
Error occurred while executing custom post portal template creation code due to {0}.

Category:
Other

Cause:
Error occurred while executing custom post portal template creation due to {0}.

Action:
Contact Administrator.

WCS-05299
Portal template created with the following warning(s) : {0}

Category:
Other

Cause:
Portal was created with warnings.

Action:
Contact Administrator.

WCS-05300
Error occurred while executing custom pre portal template deletion code due to {0}.

Category:
Other

Cause:
Error occurred while executing custom pre portal template deletion due to {0}.

Action:
Contact Administrator.

WCS-05301
Error occurred while executing custom post portal template deletion code due to {0}.

Category:
Other

Cause:
Error occurred while executing custom post portal template deletion due to {0}.

Action:
Contact Administrator.

WCS-05302
Unexpected error occurred while executing pre portal creation due to {0}.

Category:
Other

Cause:
Unexpected error occurred while executing pre portal creation due to {0}.

Action:
Contact Administrator.

WCS-05303
Unable to add {0} as it conflicts with another portal on target application.

Category:
Other

Cause:
Conflict cannot be imported.

Action:
Deselect the conflict row and add again.

WCS-05309
Unexpected error occurred during updating template {0}

Category:
Other

Cause:
Unexpected error occurred during updating template {0}

Action:
Contact Administrator.

WCS-05310
Template Display Name is null

Category:
Other

Cause:
Template Display Name is null.

Action:
Enter valid values.

WCS-05311
Template display name is a reserved keyword. One of: {0}

Category:
Other

Cause:
The template display name specified was a reserved keyword

Action:
Specify a valid alphanumeric name for the template display name which excludes the following reserved keywords: webcenter, pages, page, Spaces, Space, group, groups, Space, Spaces, webcenter Space, webcenter Spaces, webcenter Portal, WebCenter Portal, WebCenter Portal Spaces, portal, webcenter administration, my Spaces, admin, last.

WCS-05312
The template display name contains invalid characters. Only alphanumeric and space characters are allowed.

Category:
Other

Cause:
Template display name contained non-alphanumeric/space characters.

Action:
Specify a valid alphanumeric name for the template display name that only contains a-z, A-Z, 0-9, _, or a space character

WCS-05313
Portal display name must contain at least one alphanumeric character

Category:
Other

Cause:
Portal display name did not contain any alphanumeric characters

Action:
Provide at least one alphanumeric character for portal display name.

WCS-05314
Portal template with display name {0} already exists.

Category:
Other

Cause:
Portal template with display name {0} already exists.

Action:
Enter another display Name.

WCS-05315
Unexpected error occurred while fetching template displayName {0}.

Category:
Other

Cause:
Template with display name {0} already exists.

Action:
Enter another display Name.

WCS-05316
Unexpected error occurred while creating role {0} for template {1}

Category:
Other

Cause:
Unexpected error occurred while creating role {0} for template {1}.

Action:
Try again after some time or Contact Administrator.

WCS-05317
Unexpected error occurred while saving members data from portal {0} to template {1}

Category:
Other

Cause:
Unexpected error occurred while saving members data from portal {0} to template {1}.

Action:
Try again after some time or contact Administrator.

WCS-05318
Unexpected error occurred while copying member from template {0} to portal {1}

Category:
Other

Cause:
Unexpected error occurred while copying member {0} whose role {1} due to {3}.

Action:
Try again after some time or Contact Administrator.

WCS-05319
Failed to retrieve security parent portal for the child portal {0}

Category:
Other

Cause:
Failure in retrieving security parent

Action:
Contact Administrator.

WCS-05320
Failed to copy security data for portal {0}

Category:
Other

Cause:
Copy of security data from the security parent failed

Action:
Contact Administrator.

WCS-05321
Failed to delete portal {0} and all its children

Category:
Other

Cause:
Deletion of portal along with children failed

Action:
Contact Administrator.

WCS-05322
Failed to retrieve parent portal for the child portal {0}

Category:
Other

Cause:
Failure in retrieving parent portal

Action:
Contact Administrator.

WCS-05323
Failed to retrieve child portals for portal {0}

Category:
Other

Cause:
Failure in retrieving child portals

Action:
Contact Administrator.

WCS-05324
Failed to set inheritance from parent for portal {0}

Category:
Other

Cause:
Failure in setting the inheritance flag for child portals

Action:
Contact Administrator.

WCS-05325
Parent portal cannot be null

Category:
Other

Cause:
Parent portal was null.

Action:
Contact Administrator

WCS-05326
Failed to set parent portal

Category:
Other

Cause:
Error in setting parent portal

Action:
Contact Administrator

WCS-05327
Unexpected error occurred while making the template {0} public.

Category:
Other

Cause:
Unexpected error occurred while making the template {0} public.

Action:
Contact Administrator

WCS-05328
Unexpected error occurred while fetching the templates.

Category:
Other

Cause:
UUnexpected error occurred while fetching the templates.

Action:
Contact Administrator

WCS-05329
Unexpected error occurred while deleting the template during overriding the template {0}.

Category:
Other

Cause:
Unexpected error occurred while deleting the template while overriding the template.

Action:
Contact Administrator or Try again after some time

WCS-05330
Unexpected error occurred while overriding the template {0}.

Category:
Other

Cause:
Unexpected error occurred while overriding the template.

Action:
Contact Administrator or Try again after some time

WCS-05331
Unexpected error occurred while saving the template permissions.

Category:
Other

Cause:
Unexpected error occurred while saving the template permissions.

Action:
Contact Administrator

WCS-05332
Unexpected error occurred while fetching the supported languages for this portal.

Category:
Other

Cause:
Unexpected error occurred while fetching the supported languages.

Action:
Contact Administrator

WCS-05333
Unexpected error occurred while launching the portal in edit mode.

Category:
Other

Cause:
Unexpected error occurred while launching the portal in edit mode.

Action:
Contact Administrator

WCS-05334
This operation is not possible on multiple portals. Select one portal to proceed with the operation.

Category:
Other

Cause:
Unable to perform the operation on multiple portals.

Action:
Contact Administrator

WCS-05335
Unexpected error occurred while launching the About Portal dialog.

Category:
Other

Cause:
Unexpected error occurred while launching the About Portal dialog.

Action:
Contact Administrator

WCS-05336
Portal not specified

Category:
Other

Cause:
The supplied portal name was null or blank.

Action:
Specify a valid portal name that is not null or blank.

WCS-05337
Membership not changed for user {0}. You cannot manage your own membership.

Category:
Other

Cause:
Changing one's own membership in a portal is not allowed.

Action:
Select users other than the current user to change their membership.

WCS-05338
Unexpected error occurred while publishing portal template(s)

Category:
Other

Cause:
Unexpected error occurred while publishing portal template(s)

Action:
Contact Administrator.

WCS-05339
Unable to create portal as the template name is not specified.

Category:
Other

Cause:
Template is not selected.

Action:
Select at least one template to create portal.

WCS-05340
Unknown errors occurred while saving the cache for portal {0}, try setting the values again in the portal administration settings.

Category:
Other

Cause:
Error while saving cache.

Action:
Retry again from Settings screen.

WCS-05341
Portal display name must be less than 200 characters.

Category:
Other

Cause:
Portal display name exceeded 200 characters.

Action:
Specify portal display name less than 200 characters.

WCS-05342
Portal name must be less than 200 characters.

Category:
Other

Cause:
Portal name exceeded 200 characters.

Action:
Specify portal name less than 200 characters.

WCS-05343
Portal template display name must be less than 200 characters.

Category:
Other

Cause:
Portal template display name exceeded 200 characters.

Action:
Specify portal template display name less than 200 characters.

WCS-05344
Portal template name must be less than 200 characters.

Category:
Other

Cause:
Portal template name exceeded 200 characters.

Action:
Specify portal template name less than 200 characters.

WCS-05345
Keywords must be less than 4000 characters.

Category:
Other

Cause:
Keywords exceeded 4000 characters.

Action:
Specify keywords less than 4000 characters.

WCS-05346
Description must be less than 4000 characters.

Category:
Other

Cause:
Description exceeded 4000 characters.

Action:
Specify description less than 4000 characters.

WCS-05347
Select at least one portal to continue the operation.

Category:
Other

Cause:
Select at least one portal to continue.

Action:
Select at least one portal to continue.

WCS-05348
Unexpected error occurred while publishing following portal template(s) {0}

Category:
Other

Cause:
Unexpected error occurred while publishing following portal template(s) {0}

Action:
Contact Administrator or try again after some time.

WCS-05349
Unexpected error occurred while launching Rename dialog

Category:
Other

Cause:
Unexpected error occurred while launching Rename dialog

Action:
Contact Administrator or try again after some time.

WCS-05350
Unexpected error occurred while launching Set Access dialog

Category:
Other

Cause:
Unexpected error occurred while launching Set Access dialog

Action:
Contact Administrator or try again after some time.

WCS-05351
Unexpected error occurred while unpublishing portal template(s)

Category:
Other

Cause:
Unexpected error occurred while unpublishing portal template(s)

Action:
Contact Administrator.

WCS-05352
Unexpected error occurred while unpublishing following portal template(s) {0}

Category:
Other

Cause:
Unexpected error occurred while unpublishing following portal template(s) {0}

Action:
Contact Administrator or try again after some time.

WCS-05353
Select at least one portal to copy data to template.

Category:
Other

Cause:
Select at least one portal to copy data to template.

Action:
Select at least one portal to copy data to template.

WCS-05354
Portal template metadata {0} not found.

Category:
Other

Cause:
Portal template metadata not found.

Action:
Portal template metadata not found.

WCS-05355
Unable to set parent for one or more selected portal(s).

Category:
Other

Cause:
Failed to set parent for selected portal(s)

Action:
Contact the administrator.

WCS-05356
The new parent {0} specified cannot be a child portal in the hierarchy of {1}.

Category:
Other

Cause:
The new parent {0} is a child portal in the hierarchy of {1}.

Action:
Choose a different parent portal

WCS-05357
The new parent is one of the selected portals for reparenting. Choose a different parent

Category:
Other

Cause:
The new parent {0} is one of the selected portal for reparenting.

Action:
Choose a different parent portal

WCS-05358
The new parent and child portal cannot be same

Category:
Other

Cause:
The new parent and child portal specified are same.

Action:
Choose a different parent portal

WCS-05359
The URL contains invalid characters

Category:
Other

Cause:
Value entered in the url is not proper

Action:
Only the following characters are allowed: A-Z, a-z, 0-9, _

WCS-05360
The URL contains non-English characters

Category:
Other

Cause:
Non-ascii, multibyte characters entered in the pretty URL

Action:
Only English names and ascii characters are supported

WCS-05361
Error occurred while fetching the custom attributes

Category:
Other

Cause:
An unexpected error occurred while fetching the custom attribute.

Action:
Contact the administrator.

WCS-05362
The archive that you are trying to import is not a valid {0} archive. Refer to the Spaces diagnostic log file for more information or contact your system administrator.

Category:
Other

Cause:
The supplied file to import was not a valid archive.

Action:
Retry the import operation with a valid archive.

WCS-05363
The URL contains invalid characters. Permitted characters: A-Z, a-z, 0-9, _

Category:
Other

Cause:
Value entered in the url is not proper

Action:
Only the following characters are allowed: A-Z, a-z, 0-9, _

WCS-05364
The portal template name contains non-English characters

Category:
Other

Cause:
Non-ascii, multibyte characters entered in the pretty URL

Action:
Only English names and ascii characters are supported

WCS-05365
Membership not changed for group {0}. You cannot manage the membership of this group because your own membership is granted through this group. Only direct members who have manage permission can manage the membership of groups.

Category:
Other

Cause:
Changing one's own membership in a portal is not allowed.

Action:
Select users other than the current user to change their membership.

WCS-05366
Unexpected error occurred while fetching list of all portals

Category:
Other

Cause:
Unexpected error occurred while fetching list of all portals

Action:
Unexpected error occurred while fetching list of all portals

WCS-05367
Unable to display the list of portals you have access on due to unexpected errors. Try again after some time or contact administrator if the problem persists.

Category:
Other

Cause:
Unexpected error occurred while fetching list of all portals

Action:
Unexpected error occurred while fetching list of all portals

WCS-05368
Portal GUID not specified

Category:
Other

Cause:
The supplied portal GUID was null or blank.

Action:
Specify a valid portal GUID that is not null or blank.

WCS-05369
Portal not found

Category:
Other

Cause:
The system could not find the specified portal.

Action:
Specify a valid portal.

WCS-05370
Internal handler error

Category:
Other

Cause:
The internal handler for portal {0} failed.

Action:
Refer to logs for more information and contact the administrator

WCS-05371
The list of portal name passed was null

Category:
Other

Cause:
The list of portal names passed to fetch the metadata was empty.

Action:
Pass a valid list of values.

WCS-05372
The customizations available in portal template {1} were not copied to portal {0} since that process was interrupted.

Category:
Other

Cause:
Thread executing the customization document copy has been cancelled.

Action:
Retry this option using mds export/import wlst commands.

WCS-05373
The customizations available in portal template {1} were not copied to portal {0} since that process has timed-out.

Category:
Other

Cause:
Thread executing the customization document copy has been timed out

Action:
Retry this option using mds export/import wlst commands.

WCS-05374
The customizations available in portal template {1} were not copied to portal {0} due to unexpected errors.

Category:
Other

Cause:
Thread executing the customization document copy has failed to unexpected errors

Action:
Retry this option using mds export/import wlst commands.

WCS-05375
The customizations available in portal {1} were not copied to portal template {0} since that process was interrupted.

Category:
Other

Cause:
Thread executing the customization document copy has been cancelled.

Action:
Retry this option using mds export/import wlst commands.

WCS-05376
The customizations available in portal {1} were not copied to portal template {0} since that process has timed-out.

Category:
Other

Cause:
Thread executing the customization document copy has been timed out

Action:
Retry this option using mds export/import wlst commands.

WCS-05377
The customizations available in portal {1} were not copied to portal template {0} due to unexpected.

Category:
Other

Cause:
Thread executing the customization document copy has failed to unexpected errors

Action:
Retry this option using mds export/import wlst commands.

WCS-05378
Unable to launch About Portal Template dialog.

Category:
Other

Cause:
Unable to launch About Portal Template dialog.

Action:
Contact Oracle Support Services

WCS-05379
Unable to perform the operation on multiple portal templates.

Category:
Other

Cause:
Unable to perform the operation on multiple portal templates.

Action:
Select a single portal template only and retry the operation

WCS-05380
Select at least one portal template to continue the operation.

Category:
Other

Cause:
Select at least one portal template to continue.

Action:
Select at least one portal template to continue.

WCS-05381
User {0} does not have permission to view portal {1}.

Category:
Other

Cause:
User {0} does not have permission to view portal {1}.

Action:
User {0} does not have permission to view portal {1}.

WCS-05382
User {0} does not have permission to manage portal {1}.

Category:
Other

Cause:
User {0} does not have permission to manage portal {1}.

Action:
User {0} does not have permission to manage portal {1}.

WCS-05383
User {0} does not have the permission to create portal {1}.

Category:
Other

Cause:
User {0} does not have the permission to create the portal.

Action:
User {0} does not have the permission to create the portal.

WCS-05384
User {0} does not have the permission to view the portal template {1}.

Category:
Other

Cause:
User {0} does not have the permission to view the portal template {1}.

Action:
User {0} does not have the permission to view the portal template {1}.

WCS-05385
User {0} does not have permission to create portal template.

Category:
Other

Cause:
User {0} does not have permission to create portal template.

Action:
User {0} does not have permission to create portal template.

WCS-05386
User {0} does not have permission to manage portal template {1}.

Category:
Other

Cause:
User {0} does not have permission to manage portal template {1}.

Action:
User {0} does not have permission to manage portal template {1}.

WCS-05387
User {0} does not have permission to edit portal {1}.

Category:
Other

Cause:
User {0} does not have permission to edit portal {1}.

Action:
User {0} does not have permission to edit portal {1}.

WCS-05388
Unexpected error occurred while creating portal {0} from portal template {1}. Try again after some time. If the problem persists, contact Administrator

Category:
Other

Cause:
Unexpected error occurred while creating portal {0} from portal template {1}.

Action:
Contact Administrator.

WCS-05389
User {0} does not have permission to manage security of portal {1}.

Category:
Other

Cause:
User {0} does not have permission to manage security of portal {1}.

Action:
Contact Administrator.

WCS-05390
Unexpected error occurred while deleting portal {0}. Try again after some time. If the problem persists, contact Administrator.

Category:
Other

Cause:
Unexpected error occurred while deleting portal {0}.

Action:
Contact Administrator.

WCS-05391
Unexpected error occurred while creating portal template {1} from portal {0}. Try again after some time. If the problem persists, contact Administrator.

Category:
Other

Cause:
Unexpected error occurred while creating portal template {1} from portal {0}.

Action:
Contact Administrator.

WCS-05392
Unexpected error occurred while deleting portal template {0}. Try again after some time. If the problem persists, contact Administrator.

Category:
Other

Cause:
An unexpected error occurred while deleting portal template {0}.

Action:
Contact Administrator.

WCS-05393
User {0} is not authorized to refresh Portal cache.

Category:
Other

Cause:
User {0} is not authorized to refresh Portal cache.

Action:
Contact Administrator.

WCS-05394
An unexpected error occurred while creating portal preference metadata.

Category:
Other

Cause:
An unexpected while creating portal preference metadata.

Action:
Contact the administrator or try again later.

WCS-05395
User {0} does not have permission to view portal {0}, the portal is not discoverable, and self-subscription is not enabled.

Category:
Other

Cause:
User {0} does not have permission to view portal {0}, the portal is not discoverable, and self-subscription is not enabled.

Action:
Contact the administrator.

WCS-05396
An unexpected error occurred while trying to drop the role {0} in portal {1}.

Category:
Other

Cause:
An unexpected error occurred while trying to drop the role {0} in portal {1}.

Action:
Contact the administrator.

WCS-05397
An unexpected error occurred while trying to set welcome message {0} for invited non-member in portal {1}.

Category:
Other

Cause:
An unexpected error occurred while trying to set welcome message {0} for invited non-member in portal {1}.

Action:
Contact the administrator.

WCS-05398
An unexpected error occurred while trying to set welcome message {0} for invited member in portal {1}.

Category:
Other

Cause:
An unexpected error occurred while trying to set welcome message {0} for invited member in portal {1}.

Action:
Contact the administrator.

WCS-05399
An unexpected error occurred while trying to set add member message {0} in portal {1}.

Category:
Other

Cause:
An unexpected error occurred while trying to set add member message {0} in portal {1}.

Action:
Contact the administrator.

WCS-05400
An unexpected error occurred while trying to get portal members.

Category:
Other

Cause:
An unexpected error occurred while trying to get portal members.

Action:
Contact the administrator.

WCS-05401
Changing role for invited members, is not supported.

Category:
Other

Cause:
Changing role for invited members, is not supported.

Action:
For changing the role of Invited Members, delete the existing invite for the member and invite the member again with the new role.

WCS-05402
Unexpected error occurred while deleting the customization documents for portal {0}.

Category:
Other

Cause:
Unexpected error occurred while deleting the customization documents for portal {0}.

Action:
Contact Administrator.

WCS-05403
Unexpected error occurred while getting Parent Display Name for portal {0} due to {1}.

Category:
Other

Cause:
Unexpected error occurred while getting Parent Display Name for portal {0} due to {1}.

Action:
Contact Administrator.

WCS-05404
Unexpected error occurred while getting URL of parent portal for portal {0} due to {1}.

Category:
Other

Cause:
Unexpected error occurred while getting URL of parent portal for portal {0} due to {1}.

Action:
Contact Administrator.

WCS-05405
Unexpected error occurred while deleting the package containing assets for portal {0}.

Category:
Other

Cause:
Unexpected error occurred while deleting the package containing generic-site-resources documents for portal {0}.

Action:
Contact Administrator.

WCS-05406
Unable to create portal as a portal with the URL or display name {0} already exists.

Category:
Other

Cause:
A portal with the specified URL or display name already exists.

Action:
Specify a unique UURL or display name for the portal.

WCS-05407
Unable to create portal as portal name is a reserved keyword. One of: {0}

Category:
Other

Cause:
The portal name specified was a reserved keyword.

Action:
Specify a valid alphanumeric name for the portal which excludes the following reserved keywords: webcenter, pages, page, Spaces, Space, group, groups, Space, Spaces,

webcenter Space, webcenter Spaces, webcenter Portal, WebCenter Portal, WebCenter Portal Spaces, portal, webcenter administration, my Spaces, admin, last.

WCS-05408
Unable to create portal as portal display name is a reserved keyword. One of: {0}

Category:
Other

Cause:
The portal display name specified was a reserved keyword

Action:
Specify a valid alphanumeric name for the portal display name which excludes the following reserved keywords: webcenter, pages, page, Spaces, Space, group, groups, Space, Spaces, webcenter Space, webcenter Spaces, webcenter Portal, WebCenter Portal, WebCenter Portal Spaces, portal, webcenter administration, my Spaces, admin, last.

WCS-05409
Simulated error condition during creation of portal {0} for internal test purposes.

Category:
Other

Cause:
Simulated error condition during creation of portal {0} for internal test purposes.

Action:
This is just for negative tests.

WCS-05410
Unexpected error occurred while deleting the portal template(s) {0}

Category:
Other

Cause:
Unexpected error occurred while deleting following portal template(s) {0}

Action:
Contact Administrator or try again after some time.

WCS-05411
Couldn''t get the first accessible page for portal {0} due to {1}.

Category:
Other

Cause:
Error in getting the first accessible page for the portal.

Action:
Contact the application administrator.

WCS-05412
Unexpected error occurred in setting {0} as parent of portal {1} due to {2}.

Category:
Other

Cause:
Error in setting the parent portal.

Action:
Contact the application administrator.

WCS-05413
Unexpected error while setting the parent to {0} due to {1}.

Category:
Other

Cause:
Error in setting the parent and security parent for the scope

Action:
Contact the application administrator.

WCS-05414
User {0} is not authorized to generate site maps for this site.

Category:
Other

Cause:
User {0} is not authorized to generate site maps for this site.

Action:
Contact the administrator.

WCS-05415
Unexpected error while getting the site map index.

Category:
Other

Cause:
Error in getting the site map index.

Action:
Contact the administrator.

WCS-05416
Unexpected error while getting the site map for portal {0}.

Category:
Other

Cause:
Error in getting the portal site map.

Action:
Contact the administrator.

WCS-05417
Unexpected error while generating the site map.

Category:
Other

Cause:
Error while generating the site map.

Action:
Contact the administrator.

WCS-05418
Unexpected error while generating the site map for portal {0}.

Category:
Other

Cause:
Error while generating the portal site map.

Action:
Contact the administrator.

WCS-05419
Unexpected error while updating the site map for portal {0}.

Category:
Other

Cause:
Error while updating the site map.

Action:
Contact the administrator.

WCS-05420
Unexpected error occurred while deleting the portal entry from default portal metadata due to {0}.

Category:
Other

Cause:
Error while deleting the portal from default portal metadta.

Action:
Contact the administrator.

WCS-05421
Unexpected error occurred while renaming the portal entry from default portal metadata due to {0}.

Category:
Other

Cause:
Error while renaming the portal from default portal metadta.

Action:
Contact the administrator.

WCS-05422
Error fetching parent space for space {0} due to {1}

Category:
Other

Cause:
Error occurred while fetching parent space.

Action:
Contact the administrator.

WCS-05423
Unexpected error occurred while fetching the Portal Manager list for space{0} due to {1}

Category:
Other

Cause:
Error occurred while fetching the list of Portal Managers.

Action:
Contact the administrator.

WCS-05424
Attribute value not specified

Category:
Other

Cause:
Attribute value cannot be null or blank.

Action:
Please enter a valid value.

WCS-05425
Attribute name not specified

Category:
Other

Cause:
Attribute name cannot be null or blank.

Action:
Please enter a valid name.

WCS-05426
Failed to update last active time for user guid {0} with exception {1}.

Category:
Other

Cause:
Unexpected error while updating last active time for user guid {0} due to exception {1}.

Action:
Contact the application administrator.

WCS-05427
Exceptions occurred while revoking role {1} for user {0} due to failures in some of the services {2}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-05428
Unexpected error occurred while revoking roles for member {0}. Refer to the diagnostic WebCenter Portal log file for more information or contact your system administrator.

Category:
Other

Cause:
Unexpected error occurred while deleting role(s).

Action:
Contact Administrator.

WCS-05429
User {0} cannot be removed from portal {1} because {0} is the only member assigned to the Portal Manager role in the portal.

Category:
Other

Cause:
You cannot remove a member from a portal if that member is the sole Portal Manager of the portal.

Action:
Assign another member as the portal manager, then proceed to remove the current user.

WCS-05430
Cannot delete portal {0} as the Portal API cannot find this portal.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05431
Cannot create portal {0} due to error encountered when creating Portal object.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05432
Cannot create portal {0} due to error encountered when updating Portal object.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05433
Cannot create portal {0} due to error encountered when updating Portal object - {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-05434
User {0} does not have the privileges required for deployment operation on Portals. Verify that the user has "Create Portal" permission while performing the deployment operation.

Category:
Other

Cause:
Verify that the user has Create Portal permission while performing the deployment operation.

Action:
Try performing the operation as an administrator.

WCS-05435
User {0} does not have the privileges required for deployment operation on portal {1}. Verify that the user has "Manage Portal" permission while performing the deployment operation.

Category:
Other

Cause:
Verify that the user has Manage Portal permission while performing the deployment operation.

Action:
Try performing the operation as an administrator.

WCS-05436
User {0} does not have the privileges required for deployment operation on Portals. Verify that the user has "Deploy" permission while performing the deployment operation.

Category:
Other

Cause:
Verify that the user has Deploy permission while performing the deployment operation.

Action:
Try performing the operation as an administrator.

WCS-05437
User {0} does not have the privileges required for propagation operation on portal {1}. Verify that the user has "Manage Portal" permission while performing the propagation operation.

Category:
Other

Cause:
Verify that the user has Manage Portal permission while performing the propagation operation.

Action:
Try performing the operation as an administrator.

WCS-05438
User {0} does not have the privileges required for propagation operation on Portals. Verify that the user has "Deploy" permission while performing the propagation operation.

Category:
Other

Cause:
Verify that the user has Deploy permission while performing the propagation operation.

Action:
Try performing the operation as an administrator.

WCS-05439
User {0} does not have the privileges required for import operation on Portals. Verify that the user has "Create Portal" permission while performing the import operation.

Category:
Other

Cause:
Verify that the user has Create Portal permission while performing the import operation.

Action:
Try performing the operation as an administrator.

WCS-05440
User {0} does not have the privileges required for import operation on Portals. Verify that the user has "Deploy" permission while performing the import operation to be able to import the shared assets.

Category:
Other

Cause:
Verify that the user has Deploy permission while performing the import operation to be able to import the shared assets.

Action:
Try performing the operation as an administrator.

WCS-05441
User {0} does not have the privileges required for this operation on portal {1}. Verify that the user has "Manage Portal" permission while performing the export, deployment or propagation operation.

Category:
Other

Cause:
Verify that the user has Manage Portal permission while performing the export, deployment or propagation operation.

Action:
Try performing the operation as an administrator.

WCS-05442
User {0} does not have the privileges required for this operation on Portals. Verify that the user has "Deploy" permission while performing the deployment or propagation operation to be able to export the shared assets.

Category:
Other

Cause:
Verify that the user has Deploy permission while performing the deployment or propagation operation to be able to export the shared assets.

Action:
Try performing the operation as an administrator.

WCS-05443
User {0} does not have the privileges required for this operation on Portal Templates.

Category:
Other

Cause:
Check if the user has required permission on Portal Templates for performing lifecycle operations.

Action:
Try performing the operation as an administrator.

WCS-05444
User {0} does not have the privileges required for this operation on the WebCenter Portal Server application.

Category:
Other

Cause:
Check if the user has required permission on WebCenter Portal Server application for performing lifecycle operations.

Action:
Try performing the operation as an administrator.

WCS-05445
User {0} does not have the privileges required for import operation on portal {1}. Verify that the user has "Manage Portal" permission while performing the import operation.

Category:
Other

Cause:
Verify that the user has Manage Portal permission while performing the import operation.

Action:
Try performing the operation as an administrator.

WCS-05446
List of Members cannot be empty

Category:
Other

Cause:
Members List passed is empty.

Action:
Please enter a valid value.

WCS-05447
Role Name cannot be empty

Category:
Other

Cause:
Role Name is empty.

Action:
Please enter a valid Role Name.

WCS-05448
Base Role Name cannot be empty

Category:
Other

Cause:
Base Role Name is empty.

Action:
Please enter a valid Base Role Name.

WCS-05449
Portal Image URL cannot be empty

Category:
Other

Cause:
Portal Image URL is empty.

Action:
Please enter a valid Image URL.

WCS-05450
Attribute type not specified

Category:
Other

Cause:
Attribute type cannot be null or blank.

Action:
Please enter a valid type.

WCS-05451
New Portal name for rename not specified

Category:
Other

Cause:
New Portal Name cannot be null or blank.

Action:
Please enter a valid Portal name.

WCS-05452
Unexpected error occurred while performing the method {0}. Contact Administrator and check the logs for more details

Category:
Other

Cause:
Runtime error occurred while performing method {0}.

Action:
Contact Administrator and check logs.

WCS-05453
Unexpected error finding portal.

Category:
Other

Cause:
An error occuring when trying to retrieve a Portal object by its identifier.

Action:
Check underlying exception for cause.

WCS-05454
Unexpected error while trying to change membership of portal {0} due to {1}

Category:
Other

Cause:
The user roles may be invalid.

Action:
Contact the portal manager for assistance and check logs.

WCS-05455
Unexpected error while trying to subscribe a user to portal{0} due to {1}

Category:
Other

Cause:
The user roles may be invalid.

Action:
Contact the portal manager for assistance and check logs.

WCS-05701
Deleting portal {0} failed

Category:
Other

Cause:
WebService API failed to execute deleting web service call.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05702
Creating portal {0} failed

Category:
Other

Cause:
WebService API failed to execute create web service call.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05703
An error occurred while revoking the roles {1} for users in portal {0}

Category:
Other

Cause:
WebService API failed to execute revoke role web service call.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05704
An error occurred while granting roles for {1} users in portal {0}

Category:
Other

Cause:
WebService API failed to execute grant role web service call.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05705
Getting portal template {0} metadata failed

Category:
Other

Cause:
WebService API failed to execute get portal template metadata web service call.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05706
Getting portal metadata {0} failed

Category:
Other

Cause:
WebService API failed to execute get portal metadata web service call.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05707
Getting portals for search string {0} failed

Category:
Other

Cause:
WebService API failed to execute get spaces web service call.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05708
Getting portal templates for search string {0} failed

Category:
Other

Cause:
WebService API failed to execute get template web service call.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05709
Setting the Custom Attributes for scope {0} failed

Category:
Other

Cause:
WebService API failed to execute Custom Attributes.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05710
An error occurred while attempting to retrieve spaces web service endpoint configured in connections.xml of caller application

Category:
Other

Cause:
Unable to retrieve spaces web service endpoint configured in caller applications connections.xml

Action:
Please check spaces web service endpoint configured in connections.xml

WCS-05711
One of the arguments passed to API call {0} is null

Category:
Other

Cause:
A null argument was passed to an API call

Action:
Ensure to invoke the API with non-null arguments

WCS-05712
No portal name is provided

Category:
Other

Cause:
Portal name is not provided

Action:
Ensure to invoke the API with non-null arguments

WCS-05713
No portal template name is provided

Category:
Other

Cause:
Portal template name is not provided

Action:
Ensure to invoke the API with non-null arguments

WCS-05714
No portal user name is provided

Category:
Other

Cause:
Portal user name is not provided

Action:
Ensure to invoke the API with non-null arguments

WCS-05715
No portal role name is provided

Category:
Other

Cause:
Portal role name is not provided

Action:
Ensure to invoke the API with non-null arguments

WCS-05716
No portal custom attribute name is provided

Category:
Other

Cause:
Portal custom attribute name is not provided

Action:
Ensure to invoke the API with non-null arguments

WCS-05717
No portal custom attribute value is provided

Category:
Other

Cause:
Portal custom attribute value is not provided

Action:
Ensure to invoke the API with non-null arguments

WCS-05718
Error while setting the new end point for the space web services

Category:
Other

Cause:
Portal web services client already has an endpoint {0}

Action:
It cannot be overridden at the runtime. Try setting it in connections.xml and restarting the application

WCS-05719
Portal web service client is null

Category:
Other

Cause:
Portal web service client is null

Action:
You need to set the context for the client and then initialize it

WCS-05720
An unexpected error occurred while instantiating space web services client

Category:
Other

Cause:
Unable to create an instance of GroupSpaceWSClient

Action:
Please verify the context parameters or contact administrator

WCS-05721
An error occurred when user {0} tried to accept invite for portal {2} with role {1}

Category:
Other

Cause:
Failed to execute acceptance of portal invite

Action:
Check the parameters being passed to the acceptInvite API or contact administrator

WCS-05722
An error occurred when user {0} tried to reject the invite for portal {1}

Category:
Other

Cause:
Failed to execute rejection of portal invite

Action:
Check the parameters being passed to the rejectInvite API or contact administrator

WCS-05723
An error occurred while fetching the roles for portal {0}

Category:
Other

Cause:
An error occurred while fetching the roles for portal {0}

Action:
Contact administrator

WCS-05724
An error occurred while inviting {0} members to portal {1}

Category:
Other

Cause:
An error occurred while inviting the members to portal {1}

Action:
Contact administrator

WCS-05725
An error occurred while creating the portal template {0} based on portal {1}

Category:
Other

Cause:
An error occurred while creating the portal template {0}

Action:
Contact Administrator

WCS-05726
An error occurred while fetching the roles for portal template {0}

Category:
Other

Cause:
An error occurred while fetching the roles for portal template {0}

Action:
Contact administrator

WCS-05727
The Service ID {0}, is invalid.

Category:
Other

Cause:
An error occurred while fetching the RSS Feed URL for the Service ID, {0}.

Action:
Contact administrator

WCS-05728
An error occurred while checking if a login user {0} is a member of portal {1}

Category:
Other

Cause:
An error occurred while checking if a login user {1} is a member of portal {0}

Action:
Contact administrator

WCS-05729
Deleting portal template {0} failed

Category:
Other

Cause:
WebService API failed to execute deleting web service call.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05730
Search on portals for search string {0} failed

Category:
Other

Cause:
WebService API failed to execute search for portals.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05731
Creation of role {0} failed in portal {1}

Category:
Other

Cause:
WebService API failed to execute create role for portals.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05732
Dropping of role {0} failed in portal {1}

Category:
Other

Cause:
WebService API failed to execute drop role for portals.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05733
Failed to get role information for identity {0} in portal {1}

Category:
Other

Cause:
WebService API failed to get role information.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05734
Failed to get member information for portal {0}

Category:
Other

Cause:
WebService API failed to get member information.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05735
Search on portal templates for search string {0} failed

Category:
Other

Cause:
WebService API failed to execute search for portal template.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05736
No image URL is provided

Category:
Other

Cause:
Image URL is not provided

Action:
Ensure to invoke the API with non-null arguments

WCS-05737
Unexpected error occurred in preparing image URL {0}

Category:
Other

Cause:
An error occurred in preparing image URL

Action:
Make sure that the URL passed is correct.

WCS-05738
Failed to grant role for some members in portal {0}.

Category:
Other

Cause:
WebService API failed to execute grant role web service call for some or all members. This may be because these members already have provided role grants.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05739
An error occurred while revoking roles for some users in portal {0}.

Category:
Other

Cause:
WebService API failed to execute revoke role web service call for some members.

Action:
Check the web service parameters, make sure the configuration is correct.

WCS-05900
Unexpected error occurred while performing operation.

Category:
Other

Cause:
Error occurred due to unknown cause

Action:
Try the operation again or contact oracle support

WCS-06001
JCR session leak: leaked {0} sessions during {1} request to URI {2}.

Category:
Other

Cause:
JCR sessions have not been returned to the pool after the request ended.

Action:
Contact Oracle Support Services.

WCS-06002
Connection "{0}" is not a content repository connection.

Category:
Other

Cause:

Action:

WCS-06004
Error getting default IdcContext for connection "{0}": {1}

Category:
Other

Cause:

Action:

WCS-06005
Error getting admin IdcContext for connection "{0}": {1}

Category:
Other

Cause:

Action:

WCS-06006
Error getting IdcClient for connection "{0}": {1}

Category:
Other

Cause:

Action:

WCS-06007
Invalid maximum binary cache entry size: {0}. The value must be a number.

Category:
Other

Cause:

Action:

WCS-06008
The connection "{0}" is not an Oracle Content Server connection.

Category:
Other

Cause:

Action:

WCS-06009
There was an error looking up connection {0}.

Category:
Other

Cause:

Action:

WCS-06902
Incomplete repository connection, cannot login.

Category:
Other

Cause:
The repository configuration details are not valid and a classpath issue prevented the loading of the underlying JCR repository.

Action:
Verify that all the configuration parameters are correct and check the message from the underlying exception.

WCS-06905
Credentials for connection {0} not found using External Application Identifier {1}.

Category:
Other

Cause:
An attempt to fetch user credentials failed. User credentials may not have been provisioned or the external application configuration may be incorrect.

Action:
Verify the external application configuration. If necessary, provision credentials for the user.

WCS-06906
invalid credentials for connection {0} using External Application Identifier {1}

Category:
Other

Cause:
An attempt to log in using the provisioned credentials failed. The user's credentials for this connection might have been changed or the external application configuration might have been incorrect.

Action:
If the provisioned credentials for the given user are not valid, then those credentials must be provisioned again. It might also be necessary to verify the external application configuration.

WCS-06908
JCR Repository creation failure.{0}

Category:
Other

Cause:
A JCR repository instance could not be created from the parameters provided.

Action:
Check the configuration parameters, and retry.

WCS-06910
External Application Definition not found using External Application Identifier {0}

Category:
Other

Cause:
An attempt to fetch user credentials failed. The External Application ID is incorrect.

Action:
Verify that the External Application definition has been created for this connection.

WCS-06911
There is no authenticated user and PUBLIC credentials are not supported for External Application ID {0}.

Category:
Other

Cause:
An attempt to fetch credentials failed because there is not currently an authenticated user and the External Application ID does not support PUBLIC credentials.

Action:
Use an External Application ID that supports PUBLIC credentials or authenticate so that no attempt to use PUBLIC credentials will occur.

WCS-06912
There is no authenticated user and the PUBLIC credentials provisioned for External Application ID {0} are not valid.

Category:
Other

Cause:
An attempt to login using PUBLIC credentials failed because the provisioned PUBLIC credentials are not valid.

Action:
Contact your system administrator and inform them that the PUBLIC credentials need to be updated or authenticate so that no attempt to utilize the PUBLIC credentials will occur.

WCS-06913
The SHARED credentials provisioned for External Application ID {0} are not valid.

Category:
Other

Cause:
An attempt to login using SHARED credentials failed because the provisioned SHARED credentials are not valid.

Action:
Contact your system administrator and inform them that the SHARED credentials need to be updated.

WCS-07001
severe internal error

Category:
Other

Cause:
An irrecoverable internal error has occurred.

Action:
Contact Oracle Support Services.

WCS-07002
error obtaining Documents service ADF configuration

Category:
Other

Cause:
An error occurred while obtaining or interpreting the DocLib section of ADF configuration.

Action:
Verify that the Documents service section of the ADF configuration is present, complete, and contains valid data.

WCS-07003
error obtaining content repository connection

Category:
Other

Cause:
A JNDI Naming Exception occurred while attempting to obtain the content repository connection.

Action:
Verify that connections.xml contains a valid entry for the content repository connection.

WCS-07004
content repository login failure

Category:
Other

Cause:
The attempt to log on to the content repository failed.

Action:
Make sure the credentials used are valid.

WCS-07005
JCR error connecting to content repository

Category:
Other

Cause:
A JCR repository exception (other than login) occurred.

Action:
Use the associated JCR exception text to diagnose the problem.

WCS-07006
runtime error obtaining content repository

Category:
Other

Cause:
An unexpected runtime exception occurred.

Action:
Use the associated runtime exception text to diagnose the problem.

WCS-07007
cannot list items in directory {0}

Category:
Other

Cause:
An error occurred while trying to list the items in the specified folder.

Action:
Make sure that the content repository connection is accessible and that the specified folder exists.

WCS-07008
cannot get breadcrumbs for directory {0}

Category:
Other

Cause:
An error occurred while trying to list the breadcrumbs items for the specified folder.

Action:
Make sure that the content repository connection is accessible and that the specified folder exists.

WCS-07010
error listing folder {0}

Category:
Other

Cause:

Action:

WCS-07011
The Rich Text Editor could not load the target document, it may have been deleted.

Category:
Other

Cause:

Action:

WCS-07012
The Rich Text Editor could not load the destination folder, it may have been deleted.

Category:
Other

Cause:

Action:

WCS-07013
No content repository connection with the name "{0}" can be found.

Category:
Other

Cause:
A JNDI Name Not Found Exception occurred while attempting to obtain the content repository connection.

Action:
Verify connections.xml contains an entry for the specified content repository connection name.

WCS-07014
An attempt to log on to the content repository did not complete within the allotted time.

Category:
Other

Cause:
The content repository may have been slowed by heavy loads or network congestion.

Action:
Wait a while, and then retry. Optionally, ask the system administrator to allocate more resources for the content repository or to lengthen the timeout period.

WCS-07015
An attempt to log on to the content repository did not succeed because the Documents service is disabled.

Category:
Other

Cause:
Login failed because the Documents service was disabled. Another login was still executing, exceeding its allotted timeout period.

Action:
Wait a while, and then retry. Optionally, ask the system administrator to allocate more resources for the content repository or to lengthen the timeout period.

WCS-07016
Cannot get the user name for the selected user.

Category:
Other

Cause:

Action:

WCS-07017
The target Content Server does not support the following query used to retrieve recent documents: {0}.

Category:
Other

Cause:
Required components may not have been installed or properly configured.

Action:
Check the Content Server installation guide for WebCenter for details on required components and their configuration.

WCS-07018
An error occurred while trying to convert the following object from {0} to {1}: {2}.

Category:
Other

Cause:

Action:

WCS-07019
Cannot create folder "{0}" in "{1}".

Category:
Other

Cause:

Action:

WCS-07020
Error refreshing the JCR session.

Category:
Other

Cause:

Action:

WCS-07021
The transferable object contains no usable data.

Category:
Other

Cause:

Action:

WCS-07022
After fail-over, failed to get the item {0} from the repository.

Category:
Other

Cause:

Action:

WCS-07023
Please refresh to see the latest content (View > Refresh Content).

Category:
Other

Cause:

Action:

WCS-07024
Please refresh to see the latest content (View > Refresh Content). You may need to navigate up the folder hierarchy before refreshing.

Category:
Other

Cause:

Action:

WCS-07025
Unable to rename the selected document.

Category:
Other

Cause:

Action:

WCS-07026
Unable to perform the operation. The document or folder may have been deleted or you do not have permission.

Category:
Other

Cause:

Action:

WCS-07027
An error occurred performing post operation refreshing. The current document or folder may have been deleted or you do not have permission.

Category:
Other

Cause:

Action:

WCS-07028
The folder being renamed no longer exists.

Category:
Other

Cause:

Action:

WCS-07029
Unable to checkout {0}. This document is already checked out.

Category:
Other

Cause:

Action:

WCS-07030
Unable to perform the current operation.

Category:
Other

Cause:

Action:

WCS-07031
Unable to delete selected documents or folders.

Category:
Other

Cause:

Action:

WCS-07032
Unable to rename the selected folder.

Category:
Other

Cause:

Action:

WCS-07033
Unable to create folder.

Category:
Other

Cause:

Action:

WCS-07034
Unable to display folder properties.

Category:
Other

Cause:

Action:

WCS-07035
Unable to create new HTML document.

Category:
Other

Cause:

Action:

WCS-07036
Unable to upload the document.

Category:
Other

Cause:

Action:

WCS-07037
Unable to edit the HTML document.

Category:
Other

Cause:

Action:

WCS-07038
Unable to display document properties.

Category:
Other

Cause:

Action:

WCS-07039
Unable to display folder properties.

Category:
Other

Cause:

Action:

WCS-07040
Unable to save folder properties.

Category:
Other

Cause:

Action:

WCS-07041
Unable to check in the document.

Category:
Other

Cause:

Action:

WCS-07042
Unable to check out the document.

Category:
Other

Cause:

Action:

WCS-07043
Unable to cancel the document check-out.

Category:
Other

Cause:

Action:

WCS-07044
Unable to view version history for the document.

Category:
Other

Cause:

Action:

WCS-07045
Unable to copy selected documents or folders.

Category:
Other

Cause:

Action:

WCS-07046
Unable to paste selected documents or folders.

Category:
Other

Cause:

Action:

WCS-07047
A document or folder with the same name exists in this folder.

Category:
Other

Cause:

Action:

WCS-07048
A document or folder with the same name exists in this folder.

Category:
Other

Cause:

Action:

WCS-07049
You do not have permission.

Category:
Other

Cause:

Action:

WCS-07050
The folder no longer exists.

Category:
Other

Cause:

Action:

WCS-07051
The selected documents or folders no longer exist.

Category:
Other

Cause:

Action:

WCS-07052
The document no longer exists.

Category:
Other

Cause:

Action:

WCS-07053
The parent folder no longer exists.

Category:
Other

Cause:

Action:

WCS-07054
The document or folder being copied/moved no longer exists or the target folder no longer exists.

Category:
Other

Cause:

Action:

WCS-07055
The parent folder is currently unavailable.

Category:
Other

Cause:

Action:

WCS-07056
One or more of the selected documents or folders no longer exists.

Category:
Other

Cause:

Action:

WCS-07057
The document being renamed no longer exists.

Category:
Other

Cause:

Action:

WCS-07058
The document or folder no longer exists.

Category:
Other

Cause:

Action:

WCS-07059
The maximum number of folders stored within a folder has been reached. Contact your systems administrator.

Category:
Other

Cause:

Action:

WCS-07060
The maximum number of documents stored within a folder has been reached. Contact your systems administrator.

Category:
Other

Cause:

Action:

WCS-07061
The document is checked out by another user.

Category:
Other

Cause:

Action:

WCS-07062
The document is checked out by user {0}.

Category:
Other

Cause:

Action:

WCS-07063
The document is not checked out.

Category:
Other

Cause:

Action:

WCS-07064
An unknown error occurred in the Oracle Content Server.

Category:
Other

Cause:

Action:

WCS-07065
The selected document or folder or its parent folder may have been deleted or your permissions may have been revoked.

Category:
Other

Cause:

Action:

WCS-07066
Unable to move selected documents or folders.

Category:
Other

Cause:

Action:

WCS-07067
A document or folder with the same name exists in this folder.

Category:
Other

Cause:

Action:

WCS-07068
A document or folder with the same name exists in this folder.

Category:
Other

Cause:

Action:

WCS-07069
The folder name contains an invalid character.

Category:
Other

Cause:

Action:

WCS-07070
The folder name is too long.

Category:
Other

Cause:

Action:

WCS-07071
Unable to save document properties.

Category:
Other

Cause:

Action:

WCS-07072
The destination cannot be a child folder of the source folder.

Category:
Other

Cause:

Action:

WCS-07073
Unable to display item properties.

Category:
Other

Cause:

Action:

WCS-07074
Unable to save item properties.

Category:
Other

Cause:

Action:

WCS-07075
No transfer data found for data flavor {0}.

Category:
Other

Cause:

Action:

WCS-07076
No value found for task flow parameter {0}.

Category:
Other

Cause:

Action:

WCS-07077
An error occurred while adding the content presenter task flow to the page.

Category:
Other

Cause:

Action:

WCS-07078
The class method "{0}.{1}" cannot be called with a null or empty argument "{2}".

Category:
Other

Cause:
The specified method call cannot be called with the specified argument with value of null.

Action:
Ensure the specified argument has a non-null value.

WCS-07079
Datasource type "{0}" was expected but found "{1}".

Category:
Other

Cause:
The configured datasource type did not match the expected datasource type.

Action:
Correct the presenter configuration to the expected datasource type.

WCS-07080
Error retrieving node(s).

Category:
Other

Cause:
An error was encountered retrieving node(s).

Action:
Please contact a system administrator for assistance.

WCS-07081
Error saving Content Presenter Configuration.

Category:
Other

Cause:
An error was encountered saving the specified configuration document.

Action:
Please contact a system administrator for assistance.

WCS-07082
Query expression must be a valid, non-empty expression.

Category:
Other

Cause:
The specified query expression was invalid.

Action:
Review the specified query expression and correct it.

WCS-07083
The datasource type "{0}" requires "{1}" to be set.

Category:
Other

Cause:
The specified datasource type is not consistent with the datasource state.

Action:
Specific datasource types require different parameters to be set. Please resolve this situation.

WCS-07084
Invalid datasource type "{0}". Valid datasource types:{1}.

Category:
Other

Cause:
The specified datasource type was invalid.

Action:
Correct the specified datasource type to one of the examples provided in the error message.

WCS-07085
The configuration {0} is required.

Category:
Other

Cause:
You have not specified the mentioned configuration item.

Action:
Make sure the mentioned configuration item is provided for this presenter instance.

WCS-07086
Both page size and maximum results are required and must be a positive integer (pageSize: {0}, maxResults:{1}).

Category:
Other

Cause:
You have not specified the page size and maximum results.

Action:
Correct the page size and maximum results.

WCS-07087
Error loading task-flow instance configuration

Category:
Other

Cause:
An error occurred while loading the task-flow instance configuration.

Action:
Check the base exception for more details.

WCS-07088
Error saving task-flow instance configuration

Category:
Other

Cause:
An error occurred while saving the task-flow instance configuration.

Action:
Check the base exception for more details.

WCS-07089
Unable to save Content Presenter configuration data.

Category:
Other

Cause:
An error occurred while saving the presenter configuration data.

Action:
Check the base exception for more details.

WCS-07090
Unable to retrieve presenter configuration data.

Category:
Other

Cause:
An error occurred while retrieving the presenter configuration data.

Action:
Check the base exception for more details.

WCS-07091
Unable to retrieve presenter template data.

Category:
Other

Cause:
An error occurred while retrieving the presenter template data.

Action:
Check the base exception for more details.

WCS-07092
An error occurred while running the query.

Category:
Other

Cause:
An error occurred while previewing the query.

Action:
Check the base exception for more details.

WCS-07093
An error occurred while retrieving the node.

Category:
Other

Cause:
An error occurred while retrieving the node.

Action:
Check the base exception for more details.

WCS-07094
Maximum results (current:{0}) must be an integer between {1} and {2}.

Category:
Other

Cause:
The value you have specified for maximum results must inclusively be between the range specified.

Action:
Correct the maximum results to be inclusively be between the specified range.

WCS-07095
An error occurred while running the query.

Category:
Other

Cause:
A general repository exception has occurred.

Action:
Check the base exception for more details.

WCS-07096
Unable to retrieve properties for the specified item.

Category:
Other

Cause:
An error occurred while retrieving properties for the specified item.

Action:
Check the base exception for more details.

WCS-07097
Unable to retrieve markup for the specified item: {0}

Category:
Other

Cause:
An error occurred while retrieving markup for the specified item.

Action:
Check the base exception for more details.

WCS-07098
Unable to delete the selected version.

Category:
Other

Cause:

Action:

WCS-07099
Unable to retrieve workflow approvers for the specified item: {0}

Category:
Other

Cause:
An error occurred while retrieving workstate approvers for the specified item.

Action:
Check the base exception for more details.

WCS-07100
Oracle Content Server error: {0}

Category:
Other

Cause:
An unexpected error occurred in the Oracle Content Server.

Action:
Check the Oracle Content Server logs for details on this exception.

WCS-07101
Repository error: {0}

Category:
Other

Cause:
An unexpected error occurred in the content repository.

Action:
Check the base exception and repository's log for more details.

WCS-07102
Repository error

Category:
Other

Cause:
An unexpected error occurred in the content repository.

Action:
Check the base exception and repository's log for more details.

WCS-07103
Unsupported repository operation

Category:
Other

Cause:
The Documents service tried to invoke an operation that is not supported by the underlying document repository.

Action:
Avoid this operation with this repository.

WCS-07104
Access Denied

Category:
Other

Cause:

Action:

WCS-07105
Versioning is not supported on this repository.

Category:
Other

Cause:

Action:

WCS-07106
Locking is not supported on this repository.

Category:
Other

Cause:

Action:

WCS-07107
The recent documents query is not supported on this repository.

Category:
Other

Cause:

Action:

WCS-07108
Repository error: {0}

Category:
Other

Cause:
An unexpected error occurred in the content repository.

Action:
Check the base exception and repository's log for more details.

WCS-07109
Unable to save Content Presenter configuration data because no content item was selected. Select a content item before proceeding further.

Category:
Other

Cause:
An error occurred while saving the presenter configuration data without a content item.

Action:
Check the base exception for more details.

WCS-07201
Unable to approve the selected document.

Category:
Other

Cause:

Action:

WCS-07202
Unable to reject the selected document.

Category:
Other

Cause:

Action:

WCS-07203
Error initializing the user security cache.

Category:
Other

Cause:

Action:

WCS-07204
Unable to create new wiki page.

Category:
Other

Cause:

Action:

WCS-07205
Unable to find parent folder.

Category:
Other

Cause:

Action:

WCS-07206
parent folder is not set.

Category:
Other

Cause:

Action:

WCS-07207
Could not retrieve links count for resource {0}.

Category:
Other

Cause:

Action:

WCS-07208
Could not retrieve tags count for resource {0}.

Category:
Other

Cause:

Action:

WCS-07209
Could not retrieve comments count for resource {0}.

Category:
Other

Cause:

Action:

WCS-07210
Could not retrieve likes count for resource {0}.

Category:
Other

Cause:

Action:

WCS-07211
Could not retrieve likes/comments count for resource {0}.

Category:
Other

Cause:

Action:

WCS-07212
Error trying to retrieve spaces page for resource {0}.

Category:
Other

Cause:

Action:

WCS-07213
Could not set the security on the folder or document.

Category:
Other

Cause:
An error occurred while trying to update the item's security.

Action:
Review the associated error messages.

WCS-07214
The Scenario datasource was not constructed correctly

Category:
Other

Cause:
Either the conductor or the scenario have not be set correctly.

Action:
Review the specified conductor service and scenario configurations to make sure they are correct.

WCS-07215
Failed to get UCM configuration settings.

Category:
Other

Cause:
An error occurred while getting configuration information from the Content Server.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07216
The workflow settings could not be saved as there are too many approvers. Please reduce the number of approvers.

Category:
Other

Cause:

Action:

WCS-07217
Unable to add the following approvers to the workflow, the approvers username limit has been reached.{0}

Category:
Other

Cause:

Action:

WCS-07218
Unknown error while retrieving recent documents

Category:
Other

Cause:
An unknown error occurred while querying for recent documents.

Action:
Check the underlying exception for more details.

WCS-07219
Invalid parameter combination: the connection name specified by resourceId = {0} is not the same as specified in parameter connectionName = {1}.

Category:
Other

Cause:

Action:

WCS-07220
Invalid parameter combination: the item identified by resourceId = {0} is not a child of startFolderPath = {1}.

Category:
Other

Cause:

Action:

WCS-07221
{0} is not a valid resource identifier.

Category:
Other

Cause:

Action:

WCS-07222
The item with resourceId = {0} does not exist or is not accessible.

Category:
Other

Cause:

Action:

WCS-07223
Invalid content id "{0}" for datasource type "{1}".

Category:
Other

Cause:
The specified content id was invalid.

Action:
Correct the specified content id to a valid id.

WCS-07225
The object is not a Document Library resource.

Category:
Other

Cause:
An unexpected condition has occurred.

Action:
Contact your Oracle support representative.

WCS-07226
Failed to set ACL on content item as item ACL has been changed concurrently.

Category:
Other

Cause:
The attempt to change the security settings has failed because the settings have already been changed by another user.

Action:
Re-try the operation against the refreshed view of the item's security policy.

WCS-07227
Modifications to an item's security policy are not supported.

Category:
Other

Cause:
An attempt has been made to modify an item's security policy.

Action:
An item's security policy must be updated entirely and not partially.

WCS-07228
Failed to set ACL on content item {0}.

Category:
Other

Cause:
The attempt to set ACL security on an Oracle Content Server repository item has failed.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07229
Failed to restore content item {0} for security settings.

Category:
Other

Cause:
The attempt to restore a content item from its identifier has failed.

Action:
Retry the security settings operation.

WCS-07230
Determining if Content Server is configured to support item level security failed.

Category:
Other

Cause:
An error occurred while getting configuration information from the Content Server.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07231
Determining if Content Server is configured to support Slide Previewer failed.

Category:
Other

Cause:
An error occurred while getting configuration information from the Content Server.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07232
Error discovering if user has admin access to file or folder.

Category:
Other

Cause:
An error occurred when trying to discover if the current user has admin capabilities for the file or folder.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07233
Cannot perform action, item is in a workflow.

Category:
Other

Cause:
An action is being attempted on a document which is in a workflow.

Action:
Retry the action, when the workflow is complete.

WCS-07234
Fetching Workflow data from Content Server failed.

Category:
Other

Cause:
An error occurred while getting workflow information from the Content Server.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07235
No connection specified for Documents to use.

Category:
Other

Cause:
An attempt was made to use Documents without explicitly specifying a connection or configuring a primary connection.

Action:
Either explicitly supply Documents with a connection or specify a primary connection in the ADF configuration.

WCS-07237
Determining if Content Server is configured with AutoVue failed.

Category:
Other

Cause:
An error occurred while getting configuration information from the Content Server.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07238
Unexpected exception: {0}

Category:
Other

Cause:
An unexpected exception occurred.

Action:
Check the server logs for details on this exception.

WCS-07239
Unexpected error

Category:
Other

Cause:
An unexpected error occurred.

Action:
Check the server logs for details on this error.

WCS-07240
Unsupported resource type

Category:
Other

Cause:
The Documents service tried to perform an operation on a resource but failed to do so because the resource type was not recognized.

Action:
Avoid this operation with this particular type of resource.

WCS-07241
Renaming the root folder is not allowed.

Category:
Other

Cause:
An attempt was made to rename the root folder.

Action:
Avoid the rename operation with the root folder.

WCS-07242
Error reading the document's content.

Category:
Other

Cause:
The document's content could not be accessed.

Action:
Verify that the document is available.

WCS-07243
Error performing paste.

Category:
Other

Cause:
An error prevented the items from being pasted at the destination folder.

Action:
Verify that the destination folder still exists, is writable, and no items with the same names exist there.

WCS-07244
When searching between dates, if the dates are not specified in ascending order, the search may not return any results.

Category:
Other

Cause:
The begin and end dates have been specified in the wrong order.

Action:
Specify the dates in ascending order.

WCS-07245
Operation not allowed on Public folders.

Category:
Other

Cause:
An attempt has been made to perform an illegal operation on a Public folder.

Action:
Do not select a Public folder when performing operations such as delete and rename. If performing a copy or move operation then select item(s) inside the Public folder, not the Public folder itself.

WCS-07246
Approver list is too large for current workflow.

Category:
Other

Cause:
Unable to save the set of approvers for the workflow as the usernames exceed the 255 character limit.

Action:
Reduce the approvers for the workflow.

WCS-07247
Could not list the items in a folder;

Category:
Other

Cause:
An error occurred while trying to list the items in a folder.

Action:
Make sure that the content repository connection is accessible and that the folder exists. Navigate to another folder in the hierarchy.

WCS-07248
Unable to open the editor.

Category:
Other

Cause:

Action:

WCS-07249
Could not connect to the content repository.

Category:
Other

Cause:
A error occurred while trying to connect to the content repository.

Action:
Make sure that the content repository is running and accessible.

WCS-07250
Provisioning of the Documents service failed.

Category:
Other

Cause:
An error occurred while trying to provision the Documents service.

Action:
Make sure that the content repository connection is accessible. Check the Oracle Content Server logs for more information.

WCS-07251
The item may have been deleted or has already been approved or rejected.

Category:
Other

Cause:

Action:

WCS-07252
{0}

Category:
Other

Cause:

Action:

WCS-07253
Unexpected error evaluating property "{0}" of base {1}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-07254
Click the blog name in the banner to refresh with the latest content.

Category:
Other

Cause:

Action:

WCS-07255
Typical causes are that you do not have permission or one or more child items are currently in an active workflow.

Category:
Other

Cause:

Action:

WCS-07256
Error while showing configure content manager pop up.

Category:
Other

Cause:

Action:

WCS-07257
Error while saving wcc pin to page definition file.

Category:
Other

Cause:

Action:

WCS-07258
Cannot find region with id {0}.

Category:
Other

Cause:

Action:

WCS-07259
Cannot find rich popup with id {0}.

Category:
Other

Cause:

Action:

WCS-07260
Error while viewing the document. Document identifier: {0}, revision identifier: {1} and document account: {2}.

Category:
Other

Cause:

Action:

WCS-07261
Error while viewing the contents of folder. Folder identifier: {0} and folder account: {1}.

Category:
Other

Cause:

Action:

WCS-07262
An error occurred while checking permission on content.

Category:
Other

Cause:

Action:

WCS-07263
Please refresh to see the latest content.

Category:
Other

Cause:

Action:

WCS-07264
An error occurred while viewing or downloading the content.

Category:
Other

Cause:

Action:

WCS-07265
An error occurred while invoking the WCC filter.

Category:
Other

Cause:
An error occurred while invoking the WCC filter

Action:
Contact Oracle Support Services.

WCS-07501
There is no role matching the given ID: {0}.

Category:
Other

Cause:
The application attempted to look up a service role with an invalid role ID.

Action:
Ensure that your application uses a valid service role ID.

WCS-07502
Cannot grant super administrator role for scope {1}.

Category:
Other

Cause:
Could not grant the super administrator role to the scope. The super administrator role can only be granted to the default scope; other roles must be granted on a portal scope.

Action:
Verify that the role mapping is correctly defined.

WCS-07503
Cannot log on to the content repository.

Category:
Other

Cause:
The username and password used for the current login were not correct.

Action:
Check the username and password.

WCS-07504
There was an unknown content repository exception.

Category:
Other

Cause:

Action:

WCS-07505
The repository login was interrupted.

Category:
Other

Cause:

Action:

WCS-07601
Unable to read document metadata ("{0}","{1}").

Category:
Other

Cause:
Generally caused by a malformed xml document.

Action:
Check the specified xml document for errors.

WCS-07602
Document metadata ("{0}","{1}") is expected to be of type "{2}", but found "{3}".

Category:
Other

Cause:
Generally caused by a malformed xml document with an incorrect namespace.

Action:
Check the specified xml document and make sure the xmlns attribute is set to 'http://xmlns.oracle.com/webcenter/content/templates/registry'.

WCS-07603
No content list template or content template found in registry("{0}","{1}").

Category:
Other

Cause:
Generally caused by an empty display template descriptor.

Action:
Check the specified xml document and make sure that either content-templates or content-list-templates are defined.

WCS-07604
Default template view named "{0}" not found for content type "{1}".

Category:
Other

Cause:
A content type has been configured in the template registry with a default template that has not been found.

Action:
Check the specified xml document and make sure a template view exists with the id of the defaultView specified on the content type.

WCS-07605
There are duplicate template categories with id "{0}".

Category:
Other

Cause:
There are duplicate template categories that are defined with the specified id.

Action:
Check the template registry document and make sure and change the name of the specified template category.

WCS-07606
There are duplicate content types by name "{0}".

Category:
Other

Cause:
There are duplicate content types that are defined with the specified name.

Action:
Check the template registry document and make sure and change the name of the specified content type.

WCS-07607
There are duplicate content repositories by name "{0}" and type "{1}".

Category:
Other

Cause:
There are duplicate content repositories that are defined with the specified name.

Action:
Check the template registry document and make sure and change the name of the specified content repository.

WCS-07608
There are duplicate template views by id "{0}".

Category:
Other

Cause:
There are duplicate template views that are defined with the specified id.

Action:
Check the template registry document and make sure and change the id of the specified template view.

WCS-07609
The class method "{0}.{1}" cannot be called with a null argument "{2}".

Category:
Other

Cause:
The specified method call cannot be called with the specified argument with value of null.

Action:
Ensure the specified argument has a non-null value.

WCS-07610
Unable to locate resource key "{0}" in bundle "{1}".

Category:
Other

Cause:
The display template registry is configured with a resource bundle and key that is unable to be found.

Action:
Check the specified resource bundle and ensure that the specified key exists.

WCS-07611
No template category defined by id "{0}".

Category:
Other

Cause:
The display template registry does not contain a category configuration by the specified id.

Action:
Add the specified category id to the template registry.

WCS-07612
No template view defined by id "{0}".

Category:
Other

Cause:
The display template registry does not contain a template configuration by the specified id.

Action:
Add the specified template id to the template registry.

WCS-07613
No template registry found in application.

Category:
Other

Cause:
The display template registry does not exist or cannot be found.

Action:
Check application configuration and ensure registry is properly configured.

WCS-07614
Default template view named "{0}" not found in template category "{1}".

Category:
Other

Cause:
A category has been configured in the template registry with a default template view that has not been found.

Action:
Check the specified xml document and make sure a template view exists with the id of the defaultView specified on the category.

WCS-07615
Default category named "{0}" not found in the registry.

Category:
Other

Cause:
A default category has been configured in the template registry that has not been found.

Action:
Check the specified xml document and make sure a the default category has been defined.

WCS-07616
No template view defined by id "{0}" and category "{1}".

Category:
Other

Cause:
The display template registry does not contain a template configuration by the specified category and view.

Action:
Add the specified template id to the template registry.

WCS-07617
A general display template error has occurred.

Category:
Other

Cause:
An unexpected exception has occurred processing the display template registry.

Action:
Review the original stacktrace cause for more information.

WCS-07618
No default template view specified for category id "{0}". Returning the default view for the default category.

Category:
Other

Cause:
The specified category in the template registry is not configured with a default view, but has been referenced using the default behavior.

Action:
Update the specified category in the template registry to configure a default view.

WCS-07619
Invalid configuration for category id "{0}". Could not find view defined for view id "{1}".

Category:
Other

Cause:
The specified category in the template registry is configured with no default templates.

Action:
Update the registry to only include a single default template for the category.

WCS-07620
Invalid configuration for category id "{0}". Multiple templates found for view id "{1}".

Category:
Other

Cause:
The specified category in the template registry is configured with multiple templates.

Action:
Update the registry to only include a single template for the category and view id combination.

WCS-07621
Invalid configuration for content type name "{0}" in repository name "{1}" configuration.

Category:
Other

Cause:
The specified category in the template registry is configured with no default templates.

Action:
Update the registry to only include a single default template for the category.

WCS-07622
Invalid configuration for content type name "{0}" in repository "{1}". Multiple default templates found.

Category:
Other

Cause:
The specified category in the template registry is configured with multiple templates.

Action:
Update the registry to only include a single template for the category and view id combination.

WCS-07701
severe internal error while getting the template view ID

Category:
Other

Cause:
An irrecoverable internal error has occurred.

Action:
Contact Oracle Support Services.

WCS-07702
Error while getting the template view ID

Category:
Other

Cause:
An error occurred while determining the template for a node.

Action:
Check the underlying exception.

WCS-07703
No request dispatcher for template viewID {0} located at {1}

Category:
Other

Cause:
An error occurred while trying to dispatch the request to the template. The target template may not exist.

Action:
Check that the target template exists.

WCS-07704
Error processing the display template include for template viewID {0} located at {1}

Category:
Other

Cause:
An error occurred while processing the template include. This may result from a syntax or logic error in the template code.

Action:
Check the underlying exception for the details of the error.

WCS-07710
Error while getting the template view ID because of null node or view, node: {0}, view: {1}

Category:
Other

Cause:

Action:

WCS-07712
Error setting up context for template. {0}

Category:
Other

Cause:
An error occurred while trying to setup the context for the template.

Action:
Check the underlying error.

WCS-07713
Internal error: illegal reentrant use of template context.

Category:
Other

Cause:
An internal error was detected, attempted reentrant use of template context.

Action:
Contact your Oracle Support representative.

WCS-07714
Error tearing down context for template. {0}

Category:
Other

Cause:
An error occurred while trying to teardown the context for the template.

Action:
Check the underlying error.

WCS-07715
Error popping context, found another template context. {0}. {1}.

Category:
Other

Cause:
An error occurred while trying to pop the context, found another template context.

Action:
Contact your Orale support representative.

WCS-07716
Error popping context, found another context. {0}.

Category:
Other

Cause:
An error occurred while trying to pop the context, found another context.

Action:
Contact your Oracle support representative.

WCS-07717
Error while invoking component.

Category:
Other

Cause:
An error occurred while invoking the template component.

Action:
Check the underlying exception.

WCS-07718
Error when resuming context: no queued context to resume.

Category:
Other

Cause:
Template context cannot be resumed, as context queue is empty.

Action:
Contact your Oracle support representative.

WCS-07719
Error when resuming context: no context to resume.

Category:
Other

Cause:
Template context cannot be resumed, as there is no context to resume.

Action:
Contact your Oracle support representative.

WCS-07720
Error retrieving Region Template from WebCenter Content.

Category:
Other

Cause:
An error occurred retrieving the Region Template from the WebCenter Content server.

Action:
Check the exception for the underlying cause.

WCS-07801
Cannot seed the WebCenter data into the content repository.

Category:
Other

Cause:
An error occurred while seeding data for the Documents service in the content repository.

Action:
Check the underlying exception and content repository log for more information.

WCS-07802
Cannot find the adf-config.xml file.

Category:
Other

Cause:
Could not find an adf-config.xml document in the classpath.

Action:
To enable the Documents service in WebCenter, ensure adf-config.xml and connections.xml containing Documents service information are on the classpath.

WCS-07803
Cannot open a connection to the Oracle Content Server.

Category:
Other

Cause:
The application failed to open a connection to the Oracle Content Server.

Action:
Check that the Oracle Content Server connection is properly configured and that the server is available.

WCS-07804
Cannot create the Security Group, {0}, in the Oracle Content Server.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07805
Cannot create the seeded role, {0}, in the Oracle Content Server.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07806
Cannot create the folder, {0}, in the folder, {1}, in the Oracle Content Server.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07807
Cannot rename the folder, {0}, to {1}, in the Oracle Content Server.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07808
Cannot delete the folder, {0}, in the Oracle Content Server.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07809
Cannot get folder with the path, {0}, from the Oracle Content Server.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07810
Error obtaining the content repository connection "{0}".

Category:
Other

Cause:
A JNDI Naming Exception occurred while attempting to obtain the content repository connection.

Action:
Verify that connections.xml contains a valid content repository connection.

WCS-07811
Unsupported repository connection "{0}" for the Documents service.

Category:
Other

Cause:
The specified content repository is not currently supported for Documents service WebCenter Portal integration. The supported content repository types is Oracle Content Server.

Action:
Verify that adf-config.xml and connections.xml contain a valid entry for the Documents service repository.

WCS-07812
Cannot remove permissions, {0}, for user/group, {1}, to the account for the folder, {2}.

Category:
Other

Cause:
The application failed to remove permissions for the user/group on the folder.

Action:
Check that the permissions and user/group are valid and that the folder exists.

WCS-07813
Cannot grant permissions, {0}, for user, {1}, to the account for the folder, {2}.

Category:
Other

Cause:
The application failed to grant permissions for the user on the folder.

Action:
Check that the permissions and user are valid and that the folder exists.

WCS-07814
Error while removing an account from all users credentials.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07816
Unable to seed the WebCenter data in the Oracle Content Server repository.

Category:
Other

Cause:
A Content Server error occurred while seeding the WebCenter data in the repository.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07817
Unable to seed the Personal Folder data in the Oracle Content Server repository.

Category:
Other

Cause:
A Content Server error occurred while seeding the Personal Folder data in the repository.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07818
Cannot find the WebCenter administrators to seed in the Document Library repository.

Category:
Other

Cause:
The application failed to determine the list of WebCenter administrators.

Action:
Check the underlying exception for more information.

WCS-07819
Cannot release the session pool.

Category:
Other

Cause:
Failed to release the session pool for the content repository administrative connection.

Action:
Check the underlying exception for more information.

WCS-07820
Cannot create a search result row from the JCR node.

Category:
Other

Cause:

Action:

WCS-07821
Error while calling the EC_SET_PROPERTY service with dECPropType = {0}, dECPropKey = {1}, dECPropSubKey = {2}, dECPropValue = {3}.

Category:
Other

Cause:
A call to the Oracle Content Server EC_SET_PROPERTY service during repository setup failed to complete.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07822
Cannot get the WebCenter URL.

Category:
Other

Cause:

Action:

WCS-07823
Cannot grant the account, {0}, to all users.

Category:
Other

Cause:
An error occurred while trying to grant the account to all users.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07824
Unable to get the admin session to the Oracle Content Server repository.

Category:
Other

Cause:
An error occurred while trying to obtain an admin session to the Oracle Content Server repository.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07825
Cannot remove role, {0}, for user/group, {1}.

Category:
Other

Cause:
The application failed to remove the specified role from the user/group.

Action:
Check the role and user/group are valid.

WCS-07826
Cannot remove role {0} and permissions, {1}, to the account for the folder, {2} for the user/group {3}.

Category:
Other

Cause:
The application failed to remove the role and permissions on the folder for the user/group.

Action:
Check that the permissions and user/group are valid and that the folder exists.

WCS-07827
Cannot add role, {0}, for user/group, {1}.

Category:
Other

Cause:
The application failed to add the specified role to the user/group.

Action:
Check the role and user/group are valid.

WCS-07828
Cannot add role {0} and permissions, {1}, to the account for the folder, {2} for the user/group {3}.

Category:
Other

Cause:
The application failed to add the role and permissions on the folder for the user/group.

Action:
Check that the permissions and user/group are valid and that the folder exists.

WCS-07829
Cannot update the account for the portal {0}, with permission, {1}, for all users.

Category:
Other

Cause:
An error occurred while trying to update the portal account for all users.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07830
Cannot set default attributes, {0}, for the key, {1}

Category:
Other

Cause:
An error occurred while trying to set default attributes for the specified key.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07831
Cannot delete default attributes for the key, {0}.

Category:
Other

Cause:
An error occurred while trying to delete default attributes for the specified key.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07832
Cannot determine account and permission from the default attributes for the portal, {0}.

Category:
Other

Cause:
An error occurred while trying to determine the account and permission from the default attributes for the portal. The default attributes are not in the correct format.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07833
The Java Object Cache is not available.

Category:
Other

Cause:
An error occurred while trying to retrieve the cache.

Action:
Check the underlying exception for more information.

WCS-07834
A Java Object Cache operation timed out. Distributed caches may be inconsistent.

Category:
Other

Cause:
A cache operation timed out.

Action:
Check the underlying exception for more information.

WCS-07835
Java Object Cache, Put operation failed.

Category:
Other

Cause:
A cache put operation failed.

Action:
Check the underlying exception for more information.

WCS-07836
Java Object Cache, Destroy operation failed.

Category:
Other

Cause:
A cache destroy operation failed.

Action:
Check the underlying exception for more information.

WCS-07837
Java Object Cache, Get operation failed.

Category:
Other

Cause:
A cache get operation failed.

Action:
Check the underlying exception for more information.

WCS-07838
Java Object Cache, release ownership failed.

Category:
Other

Cause:
A cache unlock operation on a cached object failed.

Action:
Check the underlying exception for more information.

WCS-07839
Invalid document service ADF configuration.

Category:
Other

Cause:
The documents services configuration in adf-config.xml is invalid.

Action:
Verify that the documents services configuration in adf-config.xml conforms to the documents service configuration data schema.

WCS-07840
Cannot get folder with the GUID, {0}, from the Oracle Content Server.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07845
Error loading Site Studio content.

Category:
Other

Cause:
An error occurred while loading data for Site Studio into the content repository.

Action:
Check the underlying exception and content repository log for more information.

WCS-07846
Error checking Site Studio content into Content Server.

Category:
Other

Cause:
An error occurred while checking in Site Studio content into the content repository.

Action:
Check the underlying exception and content repository log for more information.

WCS-07847
Error checking installation of SiteStudio on Content Server.

Category:
Other

Cause:
An error occurred while checking the installation of the Site Studio in the content repository.

Action:
Check the underlying exception and content repository log for more information.

WCS-07848
Error creating temporary directory to extract SiteStudio content to.

Category:
Other

Cause:
An error occurred while creating the directory to extract the Site Studio content to.

Action:
Check the underlying exception for more information.

WCS-07850
Failed to destroy Java Object Cache region, {0}.

Category:
Other

Cause:
An error occurred while trying to destroy the Doclib Java Object Cache region.

Action:
Check the underlying exception for more information.

WCS-07857
Cannot get the version for the {0} component from the Oracle Content Server.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07863
Cannot determine if Document Library supports Enterprise Roles.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07864
Cannot enable the workflow {0}.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07865
Cannot create the workflow with the name {0}.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07866
Cannot create the workflow step {0} for the workflow {1}.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07867
Cannot get the portal account from the GUID {0}.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07868
Cannot propagate account for the portal folder {0} to its contents.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07870
Security settings are only supported for Oracle Content Server.

Category:
Other

Cause:
An attempt has been made to set security for a non Oracle Content Server repository.

Action:
To enable security, use Oracle Content Server.

WCS-07871
Cannot set default attributes, for the key, {1}

Category:
Other

Cause:
An error occurred while trying to get default attributes for the specified key.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07872
Unable to upgrade the WebCenter data in the Oracle Content Server repository.

Category:
Other

Cause:
A Content Server error occurred while upgrading the WebCenter data in the repository.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07873
Cannot get the workflow {0}.

Category:
Other

Cause:
A Content Server error occurred while getting the workflow.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07874
The documents services configuration in adf-config.xml is invalid, one of the settings is being used in another Webcenter's configuration.

Category:
Other

Cause:
Either the portal root or application name in the Document Properties is the same as another WebCenter instance using the same Content Server.

Action:
Ensure the portal root and application are both unique and not being used in another WebCenter's configuration using the same Content Server.

WCS-07875
Can not get the folder metadata for the scope, {0}.

Category:
Other

Cause:
A Content Server error occurred while getting the scope's folder metadata.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07877
Error invalidating the VCR cache entry for {0}.

Category:
Other

Cause:
An error happened while trying to remove an item from the VCR cache.

Action:
Check the underlying exception for more information.

WCS-07878
Error determining if a scope in the export set has document library provisioned.

Category:
Other

Cause:
An error happened while trying to determine if the scope is provisioned.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07879
Error while writing doclib provisioned scope to export file.

Category:
Other

Cause:
An error happened while trying to output the scopes which have document library provisioned.

Action:
Check the underlying exception for more information.

WCS-07880
Error while writing the doclib export document to MDS for portal(s) {0}.

Category:
Other

Cause:
An error happened while trying to write the document containing the document library export data to MDS.

Action:
Check the underlying exception for more information.

WCS-07884
Error while reading the set of doclib provisioned scopes from the export file.

Category:
Other

Cause:
An error happened while trying to read the scopes which have document library provisioned from the export file.

Action:
Check the underlying exception for more information.

WCS-07885
Error while reading the doclib export document from MDS for portals{0} .

Category:
Other

Cause:
An error happened while trying to read the document containing the document library export data from MDS.

Action:
Check the underlying exception for more information.

WCS-07886
Error provisioning document library for a scope in the import set.

Category:
Other

Cause:
An error happened while trying to provisioning document library during import.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07887
No document library export data found for import in MDS under path {0} for portal(s) {1}.

Category:
Other

Cause:

Action:

WCS-07888
Invalid datasource type "{0}". Valid datasource types:{1}.

Category:
Other

Cause:
The specified datasource type was invalid.

Action:
Correct the specified datasource type to one of the examples provided in the error message.

WCS-07889
Query expression must be a valid, non-empty expression.

Category:
Other

Cause:
The specified query expression was invalid.

Action:
Review the specified query expression and correct it.

WCS-07890
The Scenario datasource was not constructed correctly

Category:
Other

Cause:
Either the conductor or the scenario have not be set correctly.

Action:
Review the specified conductor service and scenario configurations to make sure they are correct.

WCS-07891
Failed to get UCM configuration settings.

Category:
Other

Cause:
An error occurred while getting configuration information from the Content Server.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07892
Invalid content id "{0}" for datasource type "{1}".

Category:
Other

Cause:
The specified content id was invalid.

Action:
Correct the specified content id to a valid id.

WCS-07893
The datasource type "{0}" requires "{1}" to be set.

Category:
Other

Cause:
The specified datasource type is not consistent with the datasource state.

Action:
Specific datasource types require different parameters to be set. Please resolve this situation.

WCS-07894
Both page size and maximum results are required and must be a positive integer (pageSize: {0}, maxResults:{1}).

Category:
Other

Cause:
You have not specified the page size and maximum results.

Action:
Correct the page size and maximum results.

WCS-07895
Maximum results (current:{0}) must be an integer between {1} and {2}.

Category:
Other

Cause:
The value you have specified for maximum results must inclusively be between the range specified.

Action:
Correct the maximum results to be inclusively be between the specified range.

WCS-07896
An error occurred while retrieving the node.

Category:
Other

Cause:
An error occurred while retrieving the node.

Action:
Check the base exception for more details.

WCS-07897
Error retrieving node(s).

Category:
Other

Cause:
An error was encountered retrieving node(s).

Action:
Please contact a system administrator for assistance.

WCS-07898
The datasource type "{0}" is currently not supported for custom folder.

Category:
Other

Cause:
The specified datasource type is not supported for ContentListFactory custom folder.

Action:
Only specific datasource types are supported. Please resolve this situation.

WCS-07899
Cannot update the seeded role, {0}, in the Oracle Content Server.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07900
Can not perform document library role mapping, role mapper is not initialized.

Category:
Other

Cause:
A Content Server error occurred while executing the operation.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07901
Can not perform document library role mapping, role mapper was initialized with a different scope to that being processed. Initialized with scope {0} and processing with scope {1}.

Category:
Other

Cause:
The document library role mapper can only process actions for the scope with which it was initialized. A request has been made to process role mapping for a different scope which is not permitted.

Action:
Check the underlying exception and Oracle Content Server log for more information.

WCS-07902
Can not perform document library role mapping, the scope does not have Document Library provisioned.

Category:
Other

Cause:
The document library role mapper can only map roles for a scope which has document library provisioned.

Action:
Check the scope has document library provisioned.

WCS-07903
Invalid repository name {0}.

Category:
Other

Cause:
An invalid repository was specified.

Action:
Verify that a valid repository is specified.

WCS-07904
Error while exporting the documents content.

Category:
Other

Cause:
An error happened while trying to export the documents content of the scopes being exported.

Action:
Check the underlying exception for more information.

WCS-07905
Error while getting the documents contents of the source scope.

Category:
Other

Cause:
An error happened while trying to get the documents of the source scope from the Content Server.

Action:
Check the underlying exception for more information.

WCS-07906
No scopes have been specified for export.

Category:
Other

Cause:
No portals have been specified to be exported.

Action:
Specify scopes to be exported.

WCS-07907
Error while importing the documents content.

Category:
Other

Cause:
An error happened while trying to import the documents content of the scopes being imported.

Action:
Check the underlying exception for more information.

WCS-07908
Group Space folder does not exist in target instance can not proceed with import.

Category:
Other

Cause:
The scope has not been provisioned in the target instance, can not proceed to import data into the target instance.

Action:
Ensure WebCenter Export Import has completed successfully and the Scope is provisioned in the target instance.

WCS-07909
The import archive {0} was not found, no document data will be imported.

Category:
Other

Cause:
The archive containing the documents data was not found. Import of documents content will not occur.

Action:
Ensure WebCenter Export included the exporting of documents content..

WCS-07910
Unable to delete data in the target scope prior to import.

Category:
Other

Cause:
An error happened while trying to delete existing data in the target scope before import commences.

Action:
Check the underlying exception for more information.

WCS-07911
Unable to create document in target scope.

Category:
Other

Cause:
An error happened while trying to create a document in the target scope.

Action:
Check the underlying exception for more information.

WCS-07916
The following documents were not imported {0}.

Category:
Other

Cause:
The documents in the list could not be imported into the target UCM.

Action:
Check the logs for more information.

WCS-07917
Error creating content URL.

Category:
Other

Cause:
An error occurred creating a content URL.

Action:
Check the underlying exception for more information.

WCS-07918
The content item {0} was not imported. An item with the filename {1} already exists in the folder.

Category:
Other

Cause:
Oracle Content Server does not permit multiple content items with the same filename to be checked into the same folder. The content item being imported has the same filename as an existing content item in the same folder. The duplicate document has not been imported.

Action:
Check the source UCM instance and either remove the duplicate content items, or ensure the import has imported the correct version of the content item.

WCS-07919
The content item {0} was not imported. The filename {1} contains an invalid characters.

Category:
Other

Cause:
The filename of the file being imported contains invalid characters, the document can not be checked in.

Action:
Check the logs for more information.

WCS-07920
An error occurred loading the names of additional content attributes.

Category:
Other

Cause:
An error occurred loading the names of additional content attributes.

Action:
Check the underlying exception for more information.

WCS-07923
No primary content repository connection.

Category:
Other

Cause:
There is no content repository connection name set as the primary connection.

Action:
Set a content repository connection as the primary connection.

WCS-07924
Error checking foldering service (Framework Folders/folders_g) of content server.

Category:
Other

Cause:
An error occurred while checking doclib foldering service implementation of content server.

Action:
Check the underlying exception and content repository log for more information.

WCS-07925
Foldering service from content server {0} and Portal Server Configuration {1} do not match.

Category:
Other

Cause:
Value stored in WC_PORTAL_PROPERTIES table and response from content server is not same.

Action:
Contact System Administrator.

WCS-07926
Framework Folders version on Oracle WebCenter Content Server is not supported for Oracle WebCenter Portal. The supported versions are {0} and later.

Category:
Other

Cause:
Framework Folders version on Oracle WebCenter Content Server is not supported for Oracle WebCenter Portal. The supported versions are 2.1 and later.

Action:
Contact System Administrator.

WCS-07927
Error creating system library list.

Category:
Other

Cause:
An error occurred while creating system library list from Oracle WebCenter Content Server.

Action:
Check the underlying exception in WebCenter Portal and Content Server logs for additional information.

WCS-07928
Failed to get document rules from Oracle WebCenter Content Server.

Category:
Other

Cause:

Action:

WCS-07929
Failed to add document rule {0} to Oracle WebCenter Content Server.

Category:
Other

Cause:

Action:

WCS-07930
An error occurred while redirecting to resource using url:{0}.

Category:
Other

Cause:

Action:

WCS-07931
An error occurred while importing portal content. Ensure that Oracle WebCenter Content Server is up and running.

Category:
Other

Cause:
An error occurred while importing portal content from Oracle WebCenter Content Server.

Action:
Check the underlying exception in WebCenter Portal and Content Server logs for additional information.

WCS-07932
Unable to get the filename for the document with ID: {0}.

Category:
Other

Cause:

Action:

WCS-07933
Error checking desktop tag component in content server.

Category:
Other

Cause:
An error occurred while checking doclib desktop tag component status in content server.

Action:
Check the underlying exception and content repository log for more information.

WCS-07934
Error seeding data for SESCrawlerExport component.

Category:
Other

Cause:
An error occurred while seeding data for SESCrawlerExport component into the content repository.

Action:
Check the underlying exception and content repository log for more information.

WCS-07935
Error loading search indexer engine name.

Category:
Other

Cause:
An error occurred while loading search indexer engine name from Oracle WebCenter Content Server.

Action:
Check the underlying exception in WebCenter Portal and Content Server logs for additional information.

WCS-07936
Error updating metadata fields used for search.

Category:
Other

Cause:
An error occurred while updating metadata fields used for search in Oracle WebCenter Content Server.

Action:
Check the underlying exception in WebCenter Portal and Content Server logs for additional information.

WCS-08001
Supplied class {0} is not an instance of {1}.

Category:
Other

Cause:
Forum service adapter details were not configured properly in the adf-config.xml file or the adapter implementation class was not correct.

Action:
Check that the adapter class name in the adf-config file is correct.

WCS-08002
Not able to invoke constructor of class {0} through Constructor.newInstance() call.

Category:
Other

Cause:
Application tried to instantiate a class through Constructor.newInstance().

Action:
Check that the adapter class name in the adf-config file is correct.

WCS-08003
Not able to find the method "{0}" in the class "{1}".

Category:
Other

Cause:
Matching constructor was not found in the adapter implementation class.

Action:
Contact Oracle Support Services.

WCS-08004
Not able to resolve the name {0}

Category:
Other

Cause:
Not able to acquire Context to look up.

Action:
Check for JNDI configuration.

WCS-08005
User "{0}" is not authorized.

Category:
Other

Cause:
Contact your administrator for access to discussions forum.

Action:
Provide valid user credentials, or check if user exists or has appropriate permissions.

WCS-08006
User "{0}" not logged on.

Category:
Other

Cause:
User might not have logged on to the system.

Action:
Try logging on using correct user credentials.

WCS-08007
User "{0}" not found

Category:
Other

Cause:
User might not have been created, or user might have been deleted from the back-end application.

Action:
Contact your administrator or try different user credentials.

WCS-08008
Service "{0}" is not a valid service or it is not supported by the "{1}" adapter implementation.

Category:
Other

Cause:
Adapter implementation does not recognize this service type.

Action:
Read the documentation for more details.

WCS-08009
Discussion forum Category with name "{0}" already exists.

Category:
Other

Cause:
Category with the given name already exists.

Action:
Try with a different category name.

WCS-08010
Category not found.

Category:
Other

Cause:
Category does not exists or user is not authorized to access it.

Action:
Provide a valid category ID.

WCS-08011
Discussion forum object Forum with name "{0}" already exists.

Category:
Other

Cause:
Discussion forum object Forum with the given name already exists.

Action:
Try with a different forum name.

WCS-08012
No forums were found.

Category:
Other

Cause:
Forum does not exists or user is not authorized to access it.

Action:
Provide a valid forum ID.

WCS-08013
Topic not found.

Category:
Other

Cause:
Topic does not exists or user is not authorized to access it.

Action:
Provide a valid topic ID.

WCS-08014
Message not found.

Category:
Other

Cause:
Message does not exists or user is not authorized to access it.

Action:
Provide a valid message ID.

WCS-08015
There is a problem with the supplied attachments.

Category:
Other

Cause:
Possible causes: attachment was larger than expected, it was not readable or available, or it was not a supported mime type.

Action:
Try with a different attachment or contact your system administrator.

WCS-08016
Unable to look up the forum connection with name "{0}".

Category:
Other

Cause:
Either the forum connection name is not valid or corresponding connection details are deleted from the connection store.

Action:
Check the default connection name in adf-config and connection details in connection store for discussion forum service or contact your system administrator.

WCS-08017
Ambiguous forum connection definitions found in the connection store.

Category:
Other

Cause:
More than 1 connection type found for discussion forum service. Unable to decide which one to use.

Action:
Configure the appropriate connection name as the default connection to use from the management console or contact your system administrator.

WCS-08018
Discussion forum object Message with subject "{0}" is prevented from being posted.

Category:
Other

Cause:
Discussion forum object Message is rejected because of any one of the following reasons: 1) blocking a set of users from posting, 2) preventing a user from posting more than once every X seconds, 3) rejecting any messages that contain profanity from the back-end application.

Action:
If you are authorized to post messages and your text has valid language, then try again after some time.

WCS-08019
Host address "{0}" configured in connection store is not correct.

Category:
Other

Cause:
IP address of the host configured in connection store could not be determined.

Action:
Configure the correct host name in connection store or contact your system administrator.

WCS-08020
Unable to connect to discussion server.

Category:
Other

Cause:
Possible reasons: The IP address of the host configured in the connection store could not be determined, or the connection was refused by the host.

Action:
Configure the correct host name in connection store or contact your system administrator.

WCS-08021
Forum connection details are not available in the connection store.

Category:
Other

Cause:
Forum connection details were not available in the connection store.

Action:
Configure discussion forum service connection details in connection store or contact your system administrator.

WCS-08022
Unable to create discussion forum object Forum with name "{0}".

Category:
Other

Cause:
Unable to create discussion forum object Forum with the supplied name and description.

Action:
Contact your administrator.

WCS-08023
Not able to reach service endpoint port type due to {0}.

Category:
Other

Cause:
Service end point is not reachable.

Action:
Contact your administrator.

WCS-08024
Input parameter value "{0}" supplied is invalid.

Category:
Other

Cause:
Invalid input parameter value is supplied.

Action:
Provide valid values for the input parameters.

WCS-08025
You do not have permission to see forums for this portal.

Category:
Other

Cause:
User is not authorized to access the forum.

Action:
Contact your administrator.

WCS-08026
You do not have permission to see recent topics for this portal.

Category:
Other

Cause:
User is not authorized to access the recent topics.

Action:
Contact your administrator.

WCS-08027
You do not have permission to see popular topics for this portal.

Category:
Other

Cause:
User is not authorized to access the popular topics.

Action:
Contact your administrator.

WCS-08028
{0} not accessible.

Category:
Other

Cause:
Contact your administrator for access.

Action:
Check if data exist or check for appropriate permissions.

WCS-08029
Could not connect to the configured discussions server.

Category:
Other

Cause:
Configured discussion server is not reachable.

Action:
Check if server details are correct or contact your administrator.

WCS-08201
Not able to create forum configuration file for community "{0}" due to : {1}.

Category:
Other

Cause:
Possible failure creating the category or forum, or an issue with the MDS write operation.

Action:
Contact your system administrator or read the discussion forum service configuration documentation for more details.

WCS-08202
Failed to flush changes into preference store due to {0}.

Category:
Other

Cause:
Possible failure in the backing store, or a failure to contact the backing store.

Action:
Contact system administrator

WCS-08601
Supplied class {0} is not an instance of {1}.

Category:
Other

Cause:
Service db adapter details were not configured properly in the adf-config.xml file or the adapter implementation class was not correct.

Action:
Check that the adapter class name in the adf-config file is correct.

WCS-08602
Not able to instantiate the class {0}, no default empty constructor found.

Category:
Other

Cause:
Application tried to instantiate a class through Constructor.newInstance().

Action:
Check that the adapter class name in the adf-config file is correct and ensure to have a default empty constructor.

WCS-08603
User "{0}" not logged on.

Category:
Other

Cause:
User might not have logged on to the system.

Action:
Try logging on using correct user credentials.

WCS-08604
Category with name "{0}" already exists.

Category:
Other

Cause:
Category with the given name already exists.

Action:
Try with a different category name.

WCS-08605
Unable to find the Category: {0}.

Category:
Other

Cause:
Category does not exists or user is not authorized to access it.

Action:
Provide a valid category ID.

WCS-08606
Unable to find the Survey {0}.

Category:
Other

Cause:
Survey does not exists or user is not authorized to access it.

Action:
Provide a valid survey ID.

WCS-08607
Survey already exists: {0}.

Category:
Other

Cause:
Survey with the given name already exists.

Action:
Try with a different survey name.

WCS-08608
Survey already closed: {0}

Category:
Other

Cause:
Survey is closed, some operations on closed surveys are not allowed.

Action:
Some operations on closed surveys are not allowed.

WCS-08609
Survey already published: {0}

Category:
Other

Cause:
Survey is published, some operations on published surveys are not allowed.

Action:
Some operations on published surveys are not allowed.

WCS-08610
Unable to find the Survey Item {0}.

Category:
Other

Cause:
Survey item does not exists.

Action:
Provide a valid survey item ID.

WCS-08611
Unable to find the Survey Template {0}.

Category:
Other

Cause:
Survey template does not exists or user is not authorized to access it.

Action:
Provide a valid survey template ID.

WCS-08612
Failed to perform {0} operation. Check logs for more details.

Category:
Other

Cause:
Unknown exception occured.

Action:
Contact your administrator to check logs for more details.

WCS-08613
Failed to perform {0} operation. Check logs for more details.

Category:
Other

Cause:
Unknown exception occured.

Action:
Contact your administrator to check logs for more details.

WCS-08614
Survey not published: {0}

Category:
Other

Cause:
Survey is not published, certain operations are not allowed without publishing.

Action:
Publish the survey to allow this operation.

WCS-09001
The IMAP host cannot be null or an empty string.

Category:
Other

Cause:
The IMAP server host address was not specified.

Action:
Configure Mail Service connection.

WCS-09002
The SMTP host cannot be null or an empty string.

Category:
Other

Cause:
The SMTP server host address was not specified.

Action:
Configure Mail Service connection.

WCS-09003
Anonymous user access is not permitted on the mail service. Users must log on to the application.

Category:
Other

Cause:
User was not logged on to the application. ADF security context was not set to authenticated user.

Action:
Log on to the application using the ADF authentication mechanism.

WCS-09004
User credentials not found in the credential store for user "{0}" with external application ID: {1}.

Category:
Other

Cause:
Mapped user credentials for the current logged on user were not found in the credential store.

Action:
Supply valid credentials.

WCS-09005
Multiple connection definitions found for mail service.

Category:
Other

Cause:
Multiple connection definitions were defined in the registry; could not identify the default connection to use.

Action:
Specify the default connection to be used in adf-config.xml. For more details, refer to the Mail Service documentation for creating connections.

WCS-09006
Lookup for connection "{0}" failed.

Category:
Other

Cause:
Failed to get the JNDI context, or the mail connection with the given name was not available.

Action:
Supply proper connection name, and ensure that the entry exists in the connection repository.

WCS-09007
ADF connections context could not be acquired. Failed to find mail connection.

Category:
Other

Cause:
Failed to get the JNDI context for the connection repository.

Action:
ADF connection context details were missing from the adf-config.xml file. For more information, refer to the ADF Developer's Guide.

WCS-09008
Failed to create mail session due to: {0}

Category:
Other

Cause:
Unexpected failure: either the IMAP/SMTP server did not respond, it failed to understand the request, or it was not configured properly.

Action:
Contact Oracle Support Services.

WCS-09009
Failed to connect to the mail server. Connection timed out.

Category:
Other

Cause:
Could not connect to the mail server in the given time.

Action:
Confirm that the IMAP/SMTP servers are running or increase the timeout value.

WCS-09010
Failed to read messages from the folder "{0}". Further information: {1}

Category:
Other

Cause:
Either the IMAP folder had issues or the search term was not supported by the server.

Action:
Contact your system administrator to check the issues in the log file.

WCS-09011
Failed to get message with ID "{0}" from the folder "{1}". Further information: {2}.

Category:
Other

Cause:
Either the IMAP folder had issues or the search term was not supported by the server.

Action:
Contact your system administrator to check the issues in the log file.

WCS-09012
Failed to send the message with subject "{0}". Further information: {1}

Category:
Other

Cause:
Either the SMTP server did not respond or the message was corrupted.

Action:
Contact your system administrator to check the issues in the log file.

WCS-09013
Message with ID "{0}" has been permanently removed from the "{1}" folder.

Category:
Other

Cause:
Either this message did not exist on the IMAP folder or it was been deleted via expunge on the folder.

Action:
The IMAP folder has been expunged to permanently delete all messages. The message cannot be recovered.

WCS-09014
Unable to find the "{0}" folder.

Category:
Other

Cause:
Either the folder with this name did not exist on the IMAP server or the mail server did not support folders.

Action:
Ensure that the folder with the given name exists and that the IMAP server is properly configured.

WCS-09015
Failed to perform the {0} operation due to: {1}.

Category:
Other

Cause:
Either the mail server was down or it did not support this operation.

Action:
Ensure that the IMAP and SMTP servers are properly configured and available.

WCS-09016
Logon failed: unknown user name or incorrect password

Category:
Other

Cause:
The user credentials acquired from the credential store were incorrect.

Action:
Ensure that the user credentials supplied for logon are correct.

WCS-09017
Could not make an attachment: not a valid body part for creating an attachment.

Category:
Other

Cause:
Either the body part was not recognized, it could not be attached to the message, or the body part could not be processed.

Action:
Contact your system Administrator.

WCS-09018
No recipients for the mail specified.

Category:
Other

Cause:
No recipients for the mail specified.

Action:
At least one recipient must be specified for the mail to be delivered.

WCS-09019
No mail connection found.

Category:
Other

Cause:
No mail connection was specified.

Action:
The mail connection is not available in the connection repository. Ensure that a connection to the mail server is defined.

WCS-09020
Connection to the server failed.

Category:
Other

Cause:
Connection to the server failed: either the host or port information was wrong or the server was down.

Action:
Check the mail server connection details and ensure that the mail server is up and running.

WCS-09021
User name to connect to the mail server for Email Gateway is not supplied.

Category:
Other

Cause:
Connection to the server failed: mail user account was not complete.

Action:
User account details are required to connect to the mail server.

WCS-09022
User password to connect to the mail server for Email Gateway is not supplied.

Category:
Other

Cause:
Connection to the server failed: mail user account is not complete.

Action:
User account details are required to connect to the mail server.

WCS-09023
Cannot attach file. Either the file exceeds the maximum allowed file size or it is empty(zero bytes). Attached files must be less than 2 MB.

Category:
Other

Cause:
Either the attachment size is 0(zero) or greater than 2 MB.

Action:
Attach a file within in the expected size limit.

WCS-09025
Message delivery failure: The message could not be sent because connecting to the SMTP mail server failed. The server may be unavailable. If the problem persists, report the error to your administrator.

Category:
Other

Cause:
Connection to the server failed: either the host or port information was wrong or the server was down.

Action:
Check the mail server connection details and ensure that the mail server is up and running.

WCS-09026
Error processing the message.

Category:
Other

Cause:
The message might have been sent with improper encoding.

Action:
Contact system administrator.

WCS-09027
The number of recipients for the mail:{0} has exceeded the maximum limit:{1} set by the space administrator.

Category:
Other

Cause:
The number of recipients for the mail has exceeded the maximum limit set by the space administrator.

Action:
Reduce the number of recipients or contact the space administrator to change the maximum limit

WCS-09201
Distribution list "{0}" already exists.

Category:
Other

Cause:
A distribution list with the supplied name already exists.

Action:
Create the distribution list with a different name.

WCS-09202
Distribution list "{0}" is not available.

Category:
Other

Cause:
A distribution list with the supplied name does not exist.

Action:
Verify the supplied name and ensure that the list exists on the mail server.

WCS-09203
Mandatory connection property "{0}" missing from the directory connection.

Category:
Other

Cause:
The mandatory connection property required to establish directory connection was not supplied.

Action:
Verify the supplied directory connection details, and ensure that the required details are supplied.

WCS-09204
Filter criteria not defined for the directory search: {0}.

Category:
Other

Cause:
Filter criteria was not defined for the directory search.

Action:
Search criteria should contain filter details.

WCS-09205
Incorrect format for the schema attribute. Value retrieved is: {0}.

Category:
Other

Cause:
The schema was not specified properly.

Action:
Check the base DN for the schema details and supply the complete base DN.

WCS-09214
Failed to acquire the initial directory context for name: {0}, due to : {1}

Category:
Other

Cause:
Failed to acquire the connection either the connection details are wrong or server is not reachable.

Action:
Ensure proper configuration is provided or Contact your administrator.

WCS-09215
Unable to create the distribution list: {0}, Mandatory attributes missing. Further information: {1}

Category:
Other

Cause:
Mandatory attributes to create a group are missing.

Action:
Contact System Administrator

WCS-09216
Unexpected error occurred. Further info: {0}

Category:
Other

Cause:
Unexpected error occurred contact system administrator.

Action:
Contact Oracle Support

WCS-09217
Unable to lookup the context name: {0}, due to : {1}

Category:
Other

Cause:
Unable to find the context.

Action:
Contact System Administrator

WCS-09218
Unable to destroy the context name: {0}, due to : {1}

Category:
Other

Cause:
Either context does not exists or its not a proper context name.

Action:
Contact System Administrator

WCS-09219
Unable to modify attributes for the context name: {0}, due to : {1}

Category:
Other

Cause:
Either context does not exists or its not a proper context name.

Action:
Contact System Administrator

WCS-09220
Unable to find the attribute: {0} under context {1}, due to {2}

Category:
Other

Cause:
Required attribute not found in the context object.

Action:
Ensure the required attribute is available in the context object.

WCS-09251
Failed to make attachment, due to: {0}.

Category:
Other

Cause:
Either the file size was too large or the selected file was not readable. Check the server settings.

Action:
Ensure that the file is available and readable. Also ensure that the file is not too large. If the problem persists, then contact your system administrator.

WCS-09252
Failed to remove attachment due to: {0}.

Category:
Other

Cause:
Either this attachment did not exist or it failed to read the message. See the error log for more details.

Action:
Contact your system administrator.

WCS-09253
Failed to send message, due to: {0}.

Category:
Other

Cause:
Either the mail session was expired or the user was not logged in.

Action:
Contact your system Administrator.

WCS-09254
Failed to read attachments, due to: {0}.

Category:
Other

Cause:
Either the mail session is expired or the user is not logged-in.

Action:
Contact your system Administrator.

WCS-09255
External application ID not defined.

Category:
Other

Cause:
The required configuration parameter External Application ID was not found.

Action:
Contact your system Administrator.

WCS-09256
This message has been deleted.

Category:
Other

Cause:
This message had been deleted.

Action:
Only non-deleted mails can be viewed.

WCS-09257
No compose message object found.

Category:
Other

Cause:
User may not be in the compose mode or the state is lost.

Action:
Ensure the user is in compose message view.

WCS-09258
Unable to find the attachment table component.

Category:
Other

Cause:
Unable to find the table component in the current view.

Action:
Ensure the table component id name is not changed.

WCS-09259
Unable to find the backing bean by name {0}.

Category:
Other

Cause:
Either the backing bean is removed or the name is changed.

Action:
Ensure the backing bean names are intact.

WCS-09501
An unexpected error occurred.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-09502
Supplied class {0} is not an instance of {1}.

Category:
Other

Cause:
Announcement service adapter details might not have been configured properly in the adf-config.xml file or adapter implementation class was not proper.

Action:
Check that the adapter class name in the adf-config file is correct.

WCS-09503
Not able to invoke constructor of class {0} through Constructor.newInstance() call.

Category:
Other

Cause:
Application is trying to instantiate a class through Constructor.newInstance().

Action:
Check that the adapter class name in the adf-config file is correct.

WCS-09504
Not able to find the method "{0}" in the class "{1}".

Category:
Other

Cause:
Matching constructor might not be found the adapter implementation class.

Action:
Contact Oracle Support Services.

WCS-09505
User "{0}" is not authorized.

Category:
Other

Cause:
Contact your administrator for access to announcements.

Action:
Provide valid user credentials, or check if user exists or has appropriate permissions.

WCS-09506
User "{0}" not logged on.

Category:
Other

Cause:
User might not have logged on to the system.

Action:
Try logging on using correct user credentials.

WCS-09507
User "{0}" is not found.

Category:
Other

Cause:
User might not have been created, or user might have been deleted from the back-end application.

Action:
Contact your administrator or try different user credentials.

WCS-09508
Announcement configuration file for community "{0}" not found or details such as category ID and announcement ID are not available.

Category:
Other

Cause:
There was a failure in creating the announcement configuration or an issue with the MDS read or write operation.

Action:
Contact your system administrator or read the announcement service configuration documentation for more details.

WCS-09509
Announcement not found.

Category:
Other

Cause:
Announcement object with the supplied announcement ID was not available or it was not accessible.

Action:
Provide a valid announcement ID.

WCS-09510
Announcement parent not found.

Category:
Other

Cause:
Announcement parent object with the supplied ID was not available or it was not accessible.

Action:
Provide a valid accessible parent ID.

WCS-09511
Announcement parent not found.

Category:
Other

Cause:
Announcement parent object is not accessible from discussion forum.

Action:
Check if discussion service is configured properly.

WCS-09512
Unable to lookup the announcement connection with name "{0}".

Category:
Other

Cause:
Either the announcement connection name is not valid or corresponding connection details are deleted from the connection store.

Action:
Check the default connection name in adf-config for discussion announcement service or contact your system administrator.

WCS-09513
Ambiguous announcement connection definitions found in the connection store.

Category:
Other

Cause:
More than 1 connection type found for discussion announcement service. Unable to decide which one to use.

Action:
Configure the appropriate connection name as the default connection to use from the management console or contact your system administrator.

WCS-09516
Announcement service configuration not found

Category:
Other

Cause:
service configuration details are missing

Action:
Ensure service config details are either loadable from classpath or from adf-config.

WCS-09517
Announcement service configuration not correct.

Category:
Other

Cause:
service configuration details are not provided as expected.

Action:
Correct the service configuration details.

WCS-09518
Host address "{0}" configured in connection store is not correct.

Category:
Other

Cause:
IP address of the host configured in connection store could not be determined.

Action:
Configure the correct host name in connection store or contact your system administrator.

WCS-09519
Not able to log on to the back-end system with host address "{0}".

Category:
Other

Cause:
Possible reasons: The IP address of the host configured in the connection store could not be determined, or the connection was refused by the host.

Action:
Configure the correct host name in connection store or contact your system administrator.

WCS-09520
Expiry date cannot be earlier than start date.

Category:
Other

Cause:
Expiry date is specified to be earlier than start date.

Action:
Specify expiry date to be later than start date.

WCS-09521
Not able to query data from SQL Connection.

Category:
Other

Cause:
Possible reasons: The database is down or invalid SQL Connection configuration in the DataSource.

Action:
Configure the correct SQL Connection in the DataSource.

WCS-09522
Announcement parent not accessible.

Category:
Other

Cause:
Contact your administrator for access to announcements.

Action:
Check if announcements parent exists or user has permissions to access announcements.

WCS-09523
Could not connect to the configured discussions server.

Category:
Other

Cause:
Configured discussion server is not reachable.

Action:
Check if server details are correct or contact your administrator.

WCS-09601
Not able to create announcement configuration file for community {0} due to : {1}.

Category:
Other

Cause:
Possible failure creating category or announcement or an issue with the MDS write operation.

Action:
Contact your system administrator or read the announcement service configuration documentation for more details.

WCS-09602
Failed to flush changes into preference store due to {0}.

Category:
Other

Cause:
Possible failure in the backing store, or failure to contact the backing store.

Action:
Contact system administrator

WCS-11001
Error on content write: {0}

Category:
Other

Cause:
The content write operation failed for the given reason.

Action:
Investigate the reason for the failure.

WCS-11002
Internal server error: {0}

Category:
Other

Cause:
An unexpected internal error has occurred.

Action:
Contact your Oracle Support representative.

WCS-11003
Invalid Request

Category:
Other

Cause:
The client has submitted an invalid HTTP request.

Action:
Re-send the corrected request.

WCS-11004
Path not found: {0}

Category:
Other

Cause:
The requested path has not been found on the server.

Action:
Correct the path on the client and re-send the request.

WCS-11005
Not an ISO8601 date: {0}

Category:
Other

Cause:
The client supplied a date which is not in ISO8601 format.

Action:
Correct the date format on the client and re-send the request.

WCS-11006
Not an HTTP date: {0}

Category:
Other

Cause:
The client supplied a date which is not in HTTP date format.

Action:
Correct the date format on the client and re-send the request.

WCS-11007
Namespace not supported: {0}

Category:
Other

Cause:
The repository does not support the given namespace.

Action:
Specify a valid namespace.

WCS-11008
Bad request

Category:
Other

Cause:
The client submitted a request that could not be understood by the server.

Action:
Correct the syntax and resubmit the request.

WCS-11009
Not modified

Category:
Other

Cause:
The client has performed a conditional GET request, access is allowed but the document has not changed.

Action:
No action required as resource has not been modified and hence it is not returned.

WCS-11010
Not acceptable

Category:
Other

Cause:
The requested resource could not generate an entity with an acceptable media-type for the client.

Action:
If applicable, resubmit the request with a broader acceptance criteria.

WCS-11011
Precondition failed

Category:
Other

Cause:
A request precondition has failed.

Action:
If applicable, resubmit the request with different preconditions.

WCS-11012
The Java virtual machine does not support the UTF-8 character set.

Category:
Other

Cause:
The UTF-8 character set is not supported by the Java virtual machine.

Action:
Contact your Oracle Support Representative.

WCS-11013
No DAV dead property name matches the JCR property name {0}.

Category:
Other

Cause:
A unexpected JCR property name has been found that does not correspond to a DAV dead property name.

Action:
Contact your Oracle Support Representative.

WCS-11014
Cannot close the servlet output stream.

Category:
Other

Cause:
There was an error closing the servlet output stream.

Action:
Review the server logs for possible cause of failure.

WCS-11015
Cannot close content input stream.

Category:
Other

Cause:
There was an error closing the content input stream.

Action:
Review the server logs for possible cause of failure.

WCS-11016
Invalid resource name: {0}

Category:
Other

Cause:
The given name is not a valid resource name.

Action:
The client should resubmit the request with a corrected URL.

WCS-11017
Invalid resource name; illegal escape sequence in path: {0}

Category:
Other

Cause:
The given name was not a valid resource name as it contains an illegal escape sequence.

Action:
The client should resubmit the request with a corrected URL.

WCS-11018
Forbidden request method: {0}

Category:
Other

Cause:
The requested HTTP method was not completed as the server forbids the execution of this type of method.

Action:
Compatible clients should not use the specified HTTP method.

WCS-11019
Folder listing is disabled.

Category:
Other

Cause:
Folder listing has been disabled.

Action:
Folder listing must be explicitly enabled in the application's web.xml.

WCS-11020
Error storing uploaded file content.

Category:
Other

Cause:
Uploaded file could not be stored.

Action:
Check other errors for cause.

WCS-11021
Error verifying CSRF token: ADF session scope token null.

Category:
Other

Cause:
CSRF could not be verified as session CSRF null.

Action:
Contact your Oracle Support representative.

WCS-11022
CSRF token check fail, session and request token mis-match.

Category:
Other

Cause:
CSRF verification failed as request and session tokens do not match.

Action:
Contact your Oracle Support representative.

WCS-11023
CSRF token check fail, session and multi-part form token mis-match. Form: {0} Session {1}

Category:
Other

Cause:
CSRF verification failed as session and multipart form tokens do not match.

Action:
Contact your Oracle Support representative.

WCS-11024
Cannot write file as CSRF not verified.

Category:
Other

Cause:
File write prohibitied as CSRF not verified.

Action:
Contact your Oracle Support representative.

WCS-11025
Error while writing response..

Category:
Other

Cause:
An error occured on sending upload response.

Action:
Check other errors for cause.

WCS-12001
Following services are not configured: {0}. Configure these services and retry the operation.

Category:
Other

Cause:
Portals imported requires some services that are not configured in the instance.

Action:
Ensure that the specified services are included and configured in the application and restart the import process.

WCS-12002
The handler found in the classpath at run time cannot process the data or metadata of the archive: {0}.

Category:
Other

Cause:
Handlers enable services to manage their data and metadata in the manner best suited to each service. The version of the handler used during import was not compatible with the version of the handler used while creating the data or metadata on export.

Action:
Include compatible versions of handlers in the application and restart the import process.

WCS-12003
The required handlers are not found: {0}.

Category:
Other

Cause:
Handlers enable services to manage their data and metadata in the manner best suited to each service. Not all handlers that were used while creating this archive could be found during the import.

Action:
Ensure that the specified services are included and configured in the application and restart the import process.

WCS-12004
Unable to retrieve the JAXB bean for the export/import document in MDS.

Category:
Other

Cause:
An error occurred in the MDS configuration of the application.

Action:
Check the MDS configuration files of the application.

WCS-12006
The export archive does not contain any scope metadata.

Category:
Other

Cause:
An error occurred during the export process, or the exported archive was damaged.

Action:
Reattempt import with a different export file.

WCS-12007
Scope with name {0} already exists in the import destination and it does not match with the scope being imported.

Category:
Other

Cause:
A scope with the specified name already exists for the current application instance. This caused a conflict between the source and target instances.

Action:
Delete the scope from the current application instance and reattempt the import.

WCS-12008
The export archive is from an older version of WebCenter Portal and is not compatible with the current version.

Category:
Other

Cause:
The export archive is created using an older version. This archive cannot be imported into the current version of WebCenter Portal.

Action:
Reattempt import with a newer export archive.

WCS-12009
The Lifecycle Manager MBean cannot be deregistered.

Category:
Other

Cause:
There are numerous possible reasons for this failure.

Action:
For information, review other messages in the log file and the reported exception stacks.

WCS-12010
The Lifecycle Manager MBean cannot be created and registered. This problem will not prevent the application from running. However, the Lifecycle Manager will be unavailable.

Category:
Other

Cause:
There are numerous possible reasons for this failure.

Action:
For information, review other messages in the log file and the reported exception stacks.

WCS-12012
Information related to run time MBeans cannot be saved in the ADFContext application scope.

Category:
Other

Cause:
The system failed to store data in the ADFContext application scope. Lifecycle functions may not be available.

Action:
Review the log files to see if there are any other problems which may have resulted in the ADFContext object becoming unusable.

WCS-12013
An internal class cast error has occurred. Actual class: {0}, cast-to class: {1}.

Category:
Other

Cause:
The possible errors could be in the code or application configuration.

Action:
Resolve any application configuration errors. If the problem recurs on subsequent attempts, then contact Oracle Support Services.

WCS-12014
The activity {0} has ended but completed less child activities ({1}) than the expected ({2}).

Category:
Other

Cause:

Action:

WCS-12015
The activity {0} has ended but completed more child activities ({1}) than the expected ({2}).

Category:
Other

Cause:

Action:

WCS-12016
The activity {0} has completed more child activities ({1}) than the expected ({2}).

Category:
Other

Cause:

Action:

WCS-12017
The export/import listener {0} has thrown an exception, which is being ignored.

Category:
Other

Cause:
A class listening to export/import progress events has thrown an exception.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12018
The resource {0} for lifecycle operation cannot be found on the classpath.

Category:
Other

Cause:

Action:

WCS-12019
The connection {0} cannot be exported because it is not a Reference or Referenceable.

Category:
Other

Cause:

Action:

WCS-12020
An error has occurred while exporting the connection {0}.

Category:
Other

Cause:

Action:

WCS-12021
The output stream for table {0} failed to close. The exception {1} will not be thrown.

Category:
Other

Cause:

Action:

WCS-12022
A SQL exception was thrown while closing the connection. This exception will be ignored.

Category:
Other

Cause:

Action:

WCS-12023
An error has occurred while closing the output stream to which the XML was being written. The export process will not be aborted.

Category:
Other

Cause:

Action:

WCS-12024
Value of the SQL type is not recognized, attempting to use the CHAR handler.

Category:
Other

Cause:

Action:

WCS-12025
Value of the SQL type is not recognized.

Category:
Other

Cause:

Action:

WCS-12026
A SQL exception {0} was caught while rolling back in response to an earlier exception {1}.

Category:
Other

Cause:

Action:

WCS-12027
A SQL exception {0} was caught while closing the statement {1}.

Category:
Other

Cause:

Action:

WCS-12028
A SQL exception {0} was caught while closing the connection {1}.

Category:
Other

Cause:

Action:

WCS-12029
An error {1} has occurred while creating a DocumentName for table {0}. The import will not be aborted.

Category:
Other

Cause:

Action:

WCS-12030
An error {1} has occurred while retrieving input stream from MDS for {0}. The import will not be aborted.

Category:
Other

Cause:

Action:

WCS-12031
An error {1} has occurred while deleting the table export document {0} from MDS. The import will not be aborted.

Category:
Other

Cause:

Action:

WCS-12032
The Queue Callback handler was interrupted while waiting for child threads to complete.

Category:
Other

Cause:

Action:

WCS-12033
Exception occurred in child thread: {0}.

Category:
Other

Cause:

Action:

WCS-12034
The Queue Consumer with name {0} was interrupted while taking an object from the queue. The Queue Consumer will continue and ignore the exception: {1}.

Category:
Other

Cause:

Action:

WCS-12038
IOException while creating stage directory for export

Category:
Other

Cause:
The possible causes could be coding, hardware, or file system errors.

Action:
Review the full exception stack for details of the exception.

WCS-12039
IOException while creating temporary directory to extract the import archive to

Category:
Other

Cause:
The possible causes could be coding, hardware, or file system errors.

Action:
Review the full exception stack for details of the exception.

WCS-12040
IOException extracting import archive

Category:
Other

Cause:
The possible causes could be coding, hardware, or file system errors.

Action:
Review the full exception stack for details of the exception.

WCS-12041
Input archive path not set on context.

Category:
Other

Cause:
The possible errors could be in the code or application configuration.

Action:
Resolve any application configuration errors. If the problem recurs on subsequent attempts, then contact Oracle Support Services.

WCS-12042
Input archive does not exist.

Category:
Other

Cause:
The possible errors could be in the code or application configuration.

Action:
Resolve any application configuration errors. If the problem recurs on subsequent attempts, then contact Oracle Support Services.

WCS-12043
MDSConfigurationException constructing source instance for MDS transfer.

Category:
Other

Cause:
The possible errors could be in the code or application configuration.

Action:
Resolve any application configuration errors. If the problem recurs on subsequent attempts, then contact Oracle Support Services.

WCS-12044
An unanticipated exception {0} has occurred while generating the oracle-archive.xml deployment descriptor of the export archive.

Category:
Other

Cause:
Cause is dependent upon the type and details of the exception being processed.

Action:
Review the exception being processed for more details.

WCS-12045
Operation aborted because of an exception thrown by subunit ({0})

Category:
Other

Cause:
The cause of the exception that was thrown is dependent upon the type and details of the exception.

Action:
Review the exception thrown for more details.

WCS-12046
MDSException while creating lifecycle document in MDS transfer source

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12047
The import archive file does not contain a metadata archive.

Category:
Other

Cause:
The supplied file to import was not a valid export archive.

Action:
Retry the import operation with a valid export archive.

WCS-12048
FileNotFoundException extracting metadata transport archive

Category:
Other

Cause:
The possible causes could be coding, hardware, or file system errors.

Action:
Resolve any hardware or file system errors. If the problem recurs on subsequent attempts, then contact Oracle Support Services.

WCS-12049
IOException while extracting metadata transport archive

Category:
Other

Cause:
The possible causes could be coding, hardware, or file system errors.

Action:
Review the full exception stack for details of the exception.

WCS-12050
IOException while creating metadata transport archive

Category:
Other

Cause:
The possible causes could be coding, hardware, or file system errors.

Action:
Review the full exception stack for details of the exception.

WCS-12051
Output path has not been set on operation context.

Category:
Other

Cause:
The possible errors could be in the code or application configuration.

Action:
Resolve any application configuration errors. If the problem recurs on subsequent attempts, then contact Oracle Support Services.

WCS-12052
MDSException constructing transfer list for MDS transfer.

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12053
MDSException performing MDS transfer.

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12054
MDSException deleting existing metadata.

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12055
An exception has occurred while creating the transformer factory to write lifecycle information document.

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12056
IOException occurred creating lifecycle information document

Category:
Other

Cause:
An error occurred writing to the file system while creating the lifecycle information document. The possible causes could be application configuration, or hardware errors.

Action:
Review the full exception stack for details of the exception.

WCS-12057
TransformerException while writing lifecycle information document

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12058
Input path has not been set on operation context.

Category:
Other

Cause:
The possible errors could be in the code or application configuration.

Action:
Resolve any application configuration errors. If the problem recurs on subsequent attempts, then contact Oracle Support Services.

WCS-12059
IOException while creating oracle-archive.xml

Category:
Other

Cause:
An error occurred while writing the oracle-archive.xml file to the file system. The possible causes could be application configuration, or hardware errors.

Action:
Review the full exception stack for details of the exception.

WCS-12060
IOException while creating transport archive

Category:
Other

Cause:
The possible causes could be coding, hardware, or file system errors.

Action:
Review the full exception stack for details of the exception.

WCS-12061
Output archive path has not been set on operation context.

Category:
Other

Cause:
The possible errors could be in the code or application configuration.

Action:
Resolve any application configuration errors. If the problem recurs on subsequent attempts, then contact Oracle Support Services.

WCS-12062
An unexpected exception occurred while removing lock {0}:{1}

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12063
MDSException occurred while removing lock {0}:{1}

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12064
A lock is blocking application import.

Category:
Other

Cause:
Another operation was being performed that prevented the import.

Action:
Retry the import operation after the other operation is complete.

WCS-12065
A lock is blocking application import.

Category:
Other

Cause:
Another operation was being performed that prevented the import.

Action:
Retry the import operation after the other operation is complete

WCS-12066
MDSException while creating application import lock

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12067
A lock is blocking the import of scope {0}.

Category:
Other

Cause:
Another operation was being performed that prevented the import.

Action:
Retry the import operation after the other operation is complete

WCS-12068
A lock exists that prevents the import of scope {0}.

Category:
Other

Cause:
An import of the specified scope was being performed that prevented this import.

Action:
Retry the import operation after the other operation is complete

WCS-12069
MDSException while creating scope import lock

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12070
A lock exists that blocks the export set import.

Category:
Other

Cause:
Another operation was being performed that prevented the export set import.

Action:
Retry the import operation after the other operation is complete

WCS-12071
A lock exists that prevents the export set import.

Category:
Other

Cause:
An export set import was already being performed preventing this import.

Action:
Retry the import operation after the other operation is complete

WCS-12072
MDSException while creating an export set import lock

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12073
MDSException while obtaining the Lifecycle bean from the MDS session

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12074
ID of export set in MDS does not match that of the application. MDS ID: {0}, Application ID: {1}.

Category:
Other

Cause:
An export set was imported from an incompatible source and has been ignored.

Action:
Import an export set from a compatible instance.

WCS-12076
NamingException while binding connection {0} to the export connections.xml

Category:
Other

Cause:
The possible causes could be coding or application configuration errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12077
NamingException while getting environment for exporting the ADF credential store

Category:
Other

Cause:
The possible causes could be coding or application configuration errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12078
IOException while exporting ADF credential store

Category:
Other

Cause:
The possible causes could be coding, hardware, or file system errors.

Action:
Review the full exception stack for details of the exception.

WCS-12079
JPSException while exporting JPS credential store

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12080
MDSException while creating lifecycle information metadata in transport set

Category:
Other

Cause:
An existing document with the same name as the lifecycle information document was found in the transport set being constructed.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12081
ReferenceException while creating lifecycle information metadata in transport set

Category:
Other

Cause:
An unexpected exception occurred while creating the lifecycle document in transport set.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12082
UnsupportedUpdateException while creating lifecycle information metadata in transport set

Category:
Other

Cause:
An unexpected exception occurred while creating the lifecycle document in the transport set.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12083
MDSException while building transfer list for lifecycle metadata

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12084
MDSException while constructing metadata store for MDS transfer

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12085
ParserConfigurationException while creating lifecycle information document

Category:
Other

Cause:
An unexpected exception occurred while creating the lifecycle document in the transport set.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12086
SAXException while creating lifecycle information document

Category:
Other

Cause:
An unexpected exception occurred while creating the lifecycle document in the transport set.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12087
ServiceException while getting registered services

Category:
Other

Cause:
There was an error in the application's configuration.

Action:
Contact Oracle Support Services.

WCS-12088
Cannot find lifecycle service extension registry

Category:
Other

Cause:
An error in the application's configuration.

Action:
Contact Oracle Support Services.

WCS-12089
Destination path specified to create the temporary directory is not a directory.

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Resolve any application configuration or hardware errors. If the problem recurs on subsequent attempts, then contact Oracle Support Services.

WCS-12090
The source path specified to archive does not exist

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Resolve any application configuration or hardware errors. If the problem recurs on subsequent attempts, then contact Oracle Support Services.

WCS-12091
The source path specified to archive is not a directory

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Resolve any application configuration or hardware errors. If the problem recurs on subsequent attempts, then contact Oracle Support Services.

WCS-12092
A file already exists with the same name as the destination folder.

Category:
Other

Cause:
A call was made to extract an archive to a destination directory with the same name as an existing file.

Action:
Retry the operation that caused this error.

WCS-12093
{0} is an invalid value for the maximum number of steps. The maximum number of steps must be a least 1.

Category:
Other

Cause:
The probable cause is a coding error.

Action:
Contact Oracle Support Services.

WCS-12094
MDSException while constructing metadata store for MDS transfer

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12095
Import archive file does not exist or could not be read.

Category:
Other

Cause:
The specified file could not be found either because it does not exist or does not have the correct access permissions.

Action:
Check that the path is correct, the file exists and has the appropriate access permissions.

WCS-12096
A lock is blocking application export.

Category:
Other

Cause:
Another operation was being performed that prevented the export.

Action:
Retry the export operation after the other operation is complete.

WCS-12097
A lock is blocking application export.

Category:
Other

Cause:
Another operation was being performed that prevented the export.

Action:
Retry the export operation after the other operation is complete

WCS-12098
MDSException while creating application export lock

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12099
An unexpected exception occurred while refreshing lock {0}:{1}

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12100
MDSException occurred while refreshing lock {0}:{1}

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12101
Unable to find data source

Category:
Other

Cause:
The data source hasn't been configured

Action:
Configure the data source

WCS-12102
An exception occurred while refreshing lock {0}:{1}

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12103
Unexpected RuntimeException performing MDS transfer.

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12104
Unexpected exception occurred while exporting portlet producer information. The producer may be down or unavailable.

Category:
Other

Cause:
The possible causes could be the portlet producer is down or unavailable, errors from the portlet producer, or application configuration.

Action:
Check that the portlet producers are available, and then retry the export. Review the full exception stack for details of the exception should it recur.

WCS-12106
Document {0} has been excluded from the export set.

Category:
Other

Cause:
The path of the document exceeds file system constraints and therefore cannot be exported.

Action:
None

WCS-12107
InvalidReferenceException constructing MDS rename plan for upgrade.

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12108
MDSException performing MDS rename for upgrade.

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12109
MDSException while committing metadata changes for upgrade.

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12110
Unable to import Scope {0} under Scope {0}

Category:
Other

Cause:
Unable to import scope under itself

Action:
Import the scope either as a root level scope or specify a different parent for the scope.

WCS-12111
Unable to import {0} as a root level scope as it inherits security.

Category:
Other

Cause:
Unable to import scope as a root level scope as it inherits security.

Action:
Import the scope as a subscope and not as a root level scope.

WCS-12112
The parent scope {0} does not exist

Category:
Other

Cause:
Unable to import as the parent scope does not exist

Action:
Import the scope either as a root level scope or specify a different parent for the scope.

WCS-12113
Export operation aborted due to the following reasons. {0}

Category:
Other

Cause:
Export operation aborted

Action:
Retry the operation fixing the cause of failure

WCS-12114
Failed to fetch the handler due to invalid resource type - {0}

Category:
Other

Cause:
Invalid Resource type is passed during import.

Action:
Retry the operation with the correct resource type.

WCS-12115
Portal Export operation aborted due to the following reasons. {0}

Category:
Other

Cause:
Backup operation aborted

Action:
Retry the operation fixing the cause of failure

WCS-12116
Exception while creating the export label

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12117
Portal {0} already exists. If you want to overwrite the portal use the "overwrite" option.

Category:
Other

Cause:
Portal already exists.

Action:
If you want to overwrite the existing portal, use the "overwrite" option.

WCS-12118
A SQL exception {0} was caught while closing the resultset.

Category:
Other

Cause:

Action:

WCS-12119
Unable to upload as the archive does not contain a shared asset.

Category:
Other

Cause:
The asset you are trying to upload belongs to a specific portal, it is not a shared asset.

Action:
Verify which portal owns the asset and then upload the asset to that portal.

WCS-12120
Unable to upload the asset as the archive does not contain an asset that belongs to this portal.

Category:
Other

Cause:
The asset you are trying to upload belongs to a different portal.

Action:
Verify which portal owns the asset and then upload the asset to that portal.

WCS-12121
A lock is blocking the deployment of portal: {0}.

Category:
Other

Cause:
Another operation was being performed that prevented the deployment.

Action:
Retry the deployment operation after the other operation is complete

WCS-12122
A lock is blocking the propagation of portal: {0}.

Category:
Other

Cause:
Another operation was being performed that prevented the propagation.

Action:
Retry the propagation operation after the other operation is complete

WCS-12123
Unable to deploy the portal "{0}" because this portal is currently being deployed to the target "{1}" by "{2}". Try again later.

Category:
Other

Cause:
Deployment of the specified portal to the specific target portal server was being performed that prevented this current deployment operation.

Action:
Retry the deployment operation after the other operation is complete

WCS-12124
Unable to deploy the portal "{0}" because changes for this portal are currently being propagated to the target "{1}" by "{2}". Try again later.

Category:
Other

Cause:
Propagation of the specified portal to the specific target portal server was being performed that prevented this current deployment operation.

Action:
Retry the deployment operation after the other operation is complete

WCS-12125
Changes for portal "{0}" cannot be propagated because this portal is currently being deployed to the target "{1}" by "{2}". Try again later.

Category:
Other

Cause:
Deployment of the specified portal to the specific target portal server was being performed that prevented this current propagation operation.

Action:
Retry the propagation operation after the other operation is complete

WCS-12126
Changes for portal "{0}" cannot be propagated because changes for this portal are currently being propagated to the target "{1}" by "{2}". Try again later.

Category:
Other

Cause:
Propagation of the specified portal to the specific target portal server was being performed that prevented this current propagation operation.

Action:
Retry the propagation operation after the other operation is complete

WCS-12127
MDSException while creating portal deployment lock

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12128
An internal error occurred while exporting portal data. Refer to the WebCenter Portal Server log for more information.

Category:
Other

Cause:
An exception was thrown while exporting the persistence data for the portal.

Action:
Retry the operation. If the exception occurs again, review the full exception stack for details.

WCS-12129
An internal error occurred while importing portal data. Refer to the WebCenter Portal Server log for more information.

Category:
Other

Cause:
An exception was thrown while importing the persistence data for the portal.

Action:
Retry the operation. If the exception occurs again, review the full exception stack for details.

WCS-12130
No user created assets of type "{0}" exist in the portal "{1}" for export.

Category:
Other

Cause:
No user created assets of the specified type exist in the portal for export.

Action:
Refresh the list of assets to see if the assets you are attempting to still exist.

WCS-12131
No user created global assets of type "{0}" exist for export.

Category:
Other

Cause:
No user created global assets of the specified type exist for export.

Action:
Refresh the list of assets to see if the assets you are attempting to still exist.

WCS-12132
Changes for portal "{0}" cannot be propagated because Oracle WebCenter Content Server is not configured properly.

Category:
Other

Cause:
Propagation of the specified portal failed because Oracle WebCenter Content Server has not been configured properly.

Action:
Retry the propagation operation after fixing the Oracle WebCenter Content Server configuration on the Oracle WebCenter Portal Server instance.

WCS-12133
Specify a valid name for the asset archive. Usage of special character / or \ is not allowed.

Category:
Other

Cause:
Usage of special character / or \ is not allowed.

Action:
Specify a valid name for the asset archive.

WCS-12134
Invalid asset archive extension provided: {0}. Specify a valid name for the asset archive using the file extension {1}.

Category:
Other

Cause:
Invalid asset archive extension specified.

Action:
Specify a valid name for the asset archive using the file extension ".aar".

WCS-12135
Specify a valid name for the asset archive using the file extension {0}.

Category:
Other

Cause:
Invalid file extension specified.

Action:
Specify a valid name for the asset archive using the file extension ".aar".

WCS-12136
An exception occurred while finding the conflicting assets.

Category:
Other

Cause:
An exception was thrown while finding the conflicting assets.

Action:
Retry the operation. If the exception occurs again, review the full exception stack for details.

WCS-12137
The archive specified is corrupted. Specify a valid archive, and try again.

Category:
Other

Cause:
The specified archive is corrupted and could not be imported.

Action:
Ensure the export archive is valid and retry the import operation.

WCS-12138
Operation aborted because of an exception thrown due to missing configuration mandated for secured lifecycle operations. Fix the configuration issues, and try again.

Category:
Other

Cause:
Operation aborted because of an exception thrown due to missing configuration mandated for secured lifecycle operations.

Action:
Retry the operation after fixing the configuration mandated for secured lifecycle operations on the Oracle WebCenter Portal Server instance.

WCS-12139
An exception occurred while calculating the checksum for the contents.

Category:
Other

Cause:
An exception occurred while calculating the checksum for the contents.

Action:
Retry the operation and review the full exception stack for details of the exception should it recur.

WCS-12140
Import and upload operations have reached the maximum number of concurrent operations allowed. Try again later.

Category:
Other

Cause:
Import and upload operations have reached the maximum number of concurrent operations allowed.

Action:
Retry the operation after any one of the concurrent operations has completed.

WCS-12141
An error occurred while deleting the portal deployment records.

Category:
Other

Cause:
The possible causes could be application configuration or hardware issues.

Action:
Retry the operation. If the error persists, review the full exception stack for details of the exception.

WCS-12900
Invalid portal template archive extension provided: {0}. Specify a valid name for the portal template archive and use the file extension {1}.

Category:
Other

Cause:
Invalid portal template archive extension specified.

Action:
Specify a valid name for the portal template archive and use the file extension '.par'

WCS-12901
An unexpected error has occurred, unable to save the archive: {0}

Category:
Other

Cause:
Unexpected erro occurred while saving the archive.

Action:
Contact Oracle Support Services.

WCS-12902
Specify an archive that exists on the server.

Category:
Other

Cause:
Unable to locate archive for import.

Action:
Specify a valid archive that exists on the server and try again.

WCS-12903
An unexpected error has occurred, unable to complete the import process.

Category:
Other

Cause:
Unable to complete the import process.

Action:
Contact Oracle Support Services.

WCS-12904
Unable to upload archive from the local file system.

Category:
Other

Cause:
Unable to upload the archive from the local file system.

Action:
Contact Oracle Support Services.

WCS-12905
Cannot save the export archive to the local file system because the file size exceeds the maximum value allowed.

Category:
Other

Cause:
Cannot save the export archive to the local file system because the file size exceeds the maximum value allowed.

Action:
Save the archive to a server and then transfer the file separately.

WCS-12906
The portal archive specified is invalid. Specify a valid archive with file extension "{0}", and try again.

Category:
Other

Cause:
Invalid portal archive extension specified.

Action:
Specify a valid name for the portal archive with the file extension '.par'

WCS-12920
A problem was encountered when invoking a method on a remote mBean ({0}) which has caused the local operation to fail.

Category:
Other

Cause:
In order for the local operation to be performed a method on a remote mBean has to be invoked - there are numerous reasons why the remote method invocation could fail ranging from connection problems between servers to the remote object simply not existing

Action:
Review the log files for a record of this error in order to ascertain the primary cause.

WCS-12950
The required customization class is not found: {0}

Category:
Other

Cause:
To export the specified customization class, first an instance of the class must be created. An instance of this class could not be created because the class was not included in the classpath.

Action:
Include the customization class in the classpath of the application and restart the application.

WCS-12951
The required customization class cannot be instantiated: {0}

Category:
Other

Cause:
To export the specified customization class, first an instance of the class must be created. An instance of this class could not be created because it is an interface or abstract class.

Action:
Contact Oracle Support Services.

WCS-12952
The required customization class cannot be instantiated: {0}

Category:
Other

Cause:
To export the specified customization class, first an instance of the class must be created. An instance of this class could not be created because the current method was unable to access it.

Action:
Contact Oracle Support Services.

WCS-12953
A listener cannot be registered to generate notification about the progress of the export. The export will continue but notification will not be generated on its progress.

Category:
Other

Cause:

Action:

WCS-12955
The notification arrived out of sequence. Latest sequence:{0}; sequence of this notification:{1}.

Category:
Other

Cause:

Action:

WCS-12957
Exception occurred while importing data. No data imported.

Category:
Other

Cause:
The issue may be due to a hardware error or an application configuration error.

Action:
Review other messages in the log file and the reported exception stacks for additional information. Resolve any application configuration or hardware errors.

WCS-12958
Import failed with errors.

Category:
Other

Cause:
The issue may be due to a hardware error or an application configuration error.

Action:
Review other messages in the log file and the reported exception stacks for additional information. Resolve any application configuration or hardware errors.

WCS-12959
Export failed with errors.

Category:
Other

Cause:
The issue may be due to a hardware error or an application configuration error.

Action:
Review other messages in the log file and the reported exception stacks for additional information. Resolve any application configuration or hardware errors.

WCS-12980
Service {0} has not been provisioned for Scope {1}.

Category:
Other

Cause:
The Service has not been provisioned for the specified Scope.

Action:
Contact Oracle Support Services.

WCS-12981
Service {0} has already been provisioned for Scope {1}.

Category:
Other

Cause:
The Service has already been provisioned for the specified Scope.

Action:
Do not provision the Service for a Scope it is already provisioned for or unprovision the Service first.

WCS-12982
Scope {0} is not known.

Category:
Other

Cause:
A Scope with the specified name has not been created.

Action:
Create a Scope with the specified name using the createScope method on the ServiceContext.

WCS-12983
Service {0} has not been configured for the application.

Category:
Other

Cause:
The Service has not been configured for the application.

Action:
Configure the Service and try the operation again.

WCS-12984
An error occurred removing the security policies for service {0}.

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Review the full exception stack for details of the exception.

WCS-12985
An error occurred invoking isProvisioned for service {0}.

Category:
Other

Cause:
The possible causes could be coding, application configuration, or hardware errors.

Action:
Review the full exception stack for details of the exception.

WCS-12986
An error occurred invoking isEnabled for service {0}.

Category:
Other

Cause:
The possible causes could be coding or application configuration.

Action:
Review the full exception stack for details of the exception.

WCS-12990
Specified key does not match that of the lock with type "{0}" and name "{1}".

Category:
Other

Cause:
The application attempted to manipulate a lock with an incorrect lock key.

Action:
Contact Oracle Support Services.

WCS-12991
Lock with type "{0}" and name "{1}" already exists.

Category:
Other

Cause:
A lock with the specified type and name already exists.

Action:
Contact Oracle Support Services.

WCS-12992
Lock with type "{0}" and name "{1}" does not exist.

Category:
Other

Cause:
The application attempted to manipulate a lock that no longer exists.

Action:
Contact Oracle Support Services.

WCS-12993
Lock with type "{0}" and name "{1}" could not be created as a lock with type "{2}" exists.

Category:
Other

Cause:
A lock with a type that prevents locks with the specified type being created exists.

Action:
Contact Oracle Support Services.

WCS-14001
An unexpected error occurred.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-14002
An object of type {0} with this id ({1}) already exits.

Category:
Other

Cause:
An attempt was made to create an object with an id that is already in use.

Action:
Specify a unique id.

WCS-14004
The name ({0}) is not valid.

Category:
Other

Cause:
The specified name is not valid.

Action:
Specify a valid name.

WCS-14005
The specified list type could not be found.

Category:
Other

Cause:
The specified list type could not be found. This may be due to the list type being deleted by another user.

Action:
Try reloading to see if the list has been deleted.

WCS-14006
Object has been changed by another user.

Category:
Other

Cause:
The object has been changed by another user.

Action:
Reload the object and try the operation again.

WCS-14007
An Object of type {0} with id={1} could not be found.

Category:
Other

Cause:
The specified object could not be found. This may be due to the list being deleted by another user.

Action:
Specify a valid id.

WCS-14008
Object ({0}) is immutable.

Category:
Other

Cause:
An attempt to change this object was made, but this object is currently immutable.

Action:
Retrieve mutable object to make changes.

WCS-14010
{0} is not a valid reference name to MDS.

Category:
Other

Cause:
The name is not a valid MDS reference name.

Action:
Contact Oracle Support Services.

WCS-14011
The MDS session does not support updates.

Category:
Other

Cause:
MDS was not configured correctly to support updates.

Action:
Configure the MDS store to support updates.

WCS-14012
An IO error occurred when accessing metadata.

Category:
Other

Cause:
An IO error occurred in MDS.

Action:
See the log for more details on the specific IO error to correct the problem.

WCS-14013
The object is not valid.

Category:
Other

Cause:
The metadata for the object does not pass validation.

Action:
Contact Oracle Support Services.

WCS-14014
Failed to construct attribute set for list [{0}].

Category:
Other

Cause:
Failed to construct attribute set for list.

Action:
Contact Oracle Support Services.

WCS-14015
Failed to add data flavor to ListTransferable. List=[{0}] DataFlavor=[{1}]

Category:
Other

Cause:
Failed to add data flavor to ListTransferable.

Action:
Contact Oracle Support Services.

WCS-14016
The query attribute predicate {0}{1}{2} was ignored because the column does not exist or the comparator is not supported.

Category:
Other

Cause:

Action:

WCS-14017
An error occurred when deleting metadata.

Category:
Other

Cause:
An error occurred in MDS while deleting metadata.

Action:
See the log for more details on the specific error to correct the problem.

WCS-14018
A column with the name ({0}) already exists.

Category:
Other

Cause:
A column was created or renamed with the name of an existing column in the list.

Action:
Specify a unique column name within the list.

WCS-14019
A list with the name ({0}) already exists.

Category:
Other

Cause:
A list was created or renamed with the name of an existing list.

Action:
Specify a unique list name.

WCS-14020
The maximum number of columns for this list has been exceeded.

Category:
Other

Cause:
A list was created or modified with more than 30 columns.

Action:
Do not add more than 30 columns to a list.

WCS-14021
User does not have permission to perform {0} operation for {1}.

Category:
Other

Cause:
User does not have permission to perform the specified operation.

Action:
Grant the user permission to perform the specified operation.

WCS-14022
The Lists service is not provisioned for scope {0}.

Category:
Other

Cause:
The Lists service is not provisioned for the specified scope.

Action:
Provision the Lists service for the specified scope.

WCS-14023
The value is the wrong data type. The data type expected is {0}.

Category:
Other

Cause:
The value is the wrong data type.

Action:
Use the value with the correct data type.

WCS-14024
The WebCenter repository is not available.

Category:
Other

Cause:
An error occurred accessing the repository.

Action:
Contact your system administrator. Check the log for more details.

WCS-14025
An error occurred accessing the WebCenter metadata repository.

Category:
Other

Cause:
An error occurred accessing the repository.

Action:
Contact your system administrator. Check the log for more details.

WCS-14026
List column values were converted or deleted based on list column changes during import: scope={0}, list={1}, column={2}.

Category:
Other

Cause:

Action:

WCS-14027
List are not enabled for this portal or a parent portal.

Category:
Other

Cause:
Lists are not enabled in this portal.

Action:
Enable lists if required by this portal.

WCS-14028
Enabling lists failed.

Category:
Other

Cause:
An error occurred enabling lists.

Action:
Contact your system administrator. Check the log for more details.

WCS-14029
Lists not enabled for portal {0}.

Category:
Other

Cause:
Lists not enabled for the specified portal.

Action:
Enable lists for the specified portal.

WCS-14501
The list was not found.

Category:
Other

Cause:
The list could not be found.

Action:
Remove the list view for the invalid list from the page.

WCS-14502
Another user deleted the row while you modified it. Discard any unsaved changes, then refresh the list.

Category:
Other

Cause:
Another user deleted the row while you modified it.

Action:
Discard any unsaved changes, then refresh the list.

WCS-14503
Another user modified a row while you modified it. Discard any unsaved changes, then refresh the list.

Category:
Other

Cause:
Another user modified a row while you modified it.

Action:
Discard any unsaved changes, then refresh the list.

WCS-14504
Another user deleted the list after you displayed it. Discard any unsaved changes, then refresh the list.

Category:
Other

Cause:
Another user deleted the list after you displayed it.

Action:
Discard any unsaved changes, then refresh the list.

WCS-14505
Another user modified this list after you displayed it. Discard any unsaved changes, then refresh the list.

Category:
Other

Cause:
Another user modified this list after you displayed it.

Action:
Discard any unsaved changes, then refresh the list.

WCS-14506
Invalid minimum/maximum range

Category:
Other

Cause:
Minimum value must be less than or equal to maximum value.

Action:
Modify the minimum value or maximum value.

WCS-14507
Default value is out of range

Category:
Other

Cause:
Default value must be between the minimum and maximum values.

Action:
Modify the default value, minimum value, or maximum value.

WCS-14508
An error occurred accessing the WebCenter repository.

Category:
Other

Cause:
An error occurred accessing the repository.

Action:
Contact your system administrator. Check the log for more details.

WCS-14509
Your permission to perform this operation was revoked. Refresh the list and discard unsaved changes.

Category:
Other

Cause:
Your permission to perform this operation was revoked.

Action:
Request permission to perform this operation.

WCS-14510
The Lists service was disabled, preventing you from performing this operation. Refresh the list and discard unsaved changes.

Category:
Other

Cause:
The Lists service was disabled, preventing you from performing this operation.

Action:
Enable the Lists service.

WCS-14514
An unexpected error occurred. Please retry the operation.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Retry the operation. If the problem persists, contact your administrator.

WCS-14515
Default value is too long

Category:
Other

Cause:
Default value must not exceed the maximum length.

Action:
Modify the default value or maximum length.

WCS-14516
The WebCenter metadata repository was temporarily unavailable. Please retry the operation.

Category:
Other

Cause:
The connection to the WebCenter metadata repository failed.

Action:
Retry the operation. If the problem persists, contact your administrator.

WCS-14517
Another user deleted the list after you displayed it. Discard any unsaved changes, then click Close to exit list edit mode.

Category:
Other

Cause:
Another user deleted the list after you displayed it.

Action:
Discard any unsaved changes, then click Close to exit list edit mode.

WCS-14518
Another user deleted the list. Click Close to exit list edit mode.

Category:
Other

Cause:
Another user deleted the list.

Action:
Click Close to exit list edit mode.

WCS-14519
The list row was not found.

Category:
Other

Cause:
The list row could not be found.

Action:
None.

WCS-14522
Lists are disabled, preventing you from performing this operation. Enable lists to continue making changes.

Category:
Other

Cause:
Lists are disabled, preventing you from performing this operation.

Action:
Enable lists.

WCS-18001
An unexpected error occurred.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18002
Missing Configuration for List of Contacts. Could not locate the class {0}.

Category:
Other

Cause:
An incorrect class name was provided.

Action:
Please contact Oracle Support.

WCS-18003
Class {0} does not implement the interface {1}.

Category:
Other

Cause:
The specified class had not implemented the required interface.

Action:
Ensure that the class implements the required interface.

WCS-18004
Cannot instantiate class {0}.

Category:
Other

Cause:
The specified class did not have a default constructor accessible to public.

Action:
Ensure that the class has a default constructor and it is accessible to public.

WCS-18005
Cannot instantiate class {0}.

Category:
Other

Cause:
Either the specified class was not a concrete implementation or it did not have a default constructor accessible to public.

Action:
Ensure that the class is a concrete implementation and has a default constructor accessible to public.

WCS-18006
The implementation class {0} returned null.

Category:
Other

Cause:
The implementation class returned a null object.

Action:
Ensure that the implementation class returns a non-null list of contacts.

WCS-18007
An error occurred while trying to validate metadata.

Category:
Other

Cause:
Invalid metadata has been introduced.

Action:
Contact Oracle Support Services.

WCS-18008
Unable to save the metadata in persistence store

Category:
Other

Cause:
An error occurred while writing to persistence store or metadata was locked by another user.

Action:
Contact Oracle Support Services.

WCS-18009
Cannot apply the current metadata changes to a concurrently modified metadata.

Category:
Other

Cause:
Recent changes in this session conflicts with changes made in the same session.

Action:
Contact Oracle Support Services.

WCS-18010
Cannot locate the requested metadata.

Category:
Other

Cause:
The metadata was not found in the configured metadata stores or it had been deleted on this session.

Action:
Contact Oracle Support Services.

WCS-18011
Cannot obtain the metadata for write operations.

Category:
Other

Cause:
The metadata store could be spanning multiple back-end stores or concurrent updates were attempted.

Action:
Contact Oracle Support Services.

WCS-18012
Metadata already exists in metadata store.

Category:
Other

Cause:
An attempt was made to create a metadata document when it already exists.

Action:
Contact Oracle Support Services.

WCS-18013
The reference to the specified metadata is invalid.

Category:
Other

Cause:
The reference to the metadata was incorrect.

Action:
Contact Oracle Support Services.

WCS-18014
Could not be complete the sort operation.

Category:
Other

Cause:
A null table component was returned.

Action:
Contact Oracle Support Services.

WCS-18015
Could not get contact details.

Category:
Other

Cause:
The selected contact details were unavailable due to an internal error.

Action:
Contact Oracle Support Services.

WCS-18016
Could not launch the dialog for view {0}.

Category:
Other

Cause:
Profile page details are unavailable due to an internal error.

Action:
Contact Oracle Support Services.

WCS-18017
Could not perform a people search.

Category:
Other

Cause:
Instance of identity store is not available.

Action:
Contact Oracle Support Services.

WCS-18018
Could not get display name from user profile.

Category:
Other

Cause:
User did not have the display name or user's profile was not accessible.

Action:
Contact the administrator of directory services/webcenter.

WCS-18019
Could not get name from user profile.

Category:
Other

Cause:
User does not have the name or user's profile is not accessible.

Action:
Please contact the administrator of directory services/webcenter.

WCS-18020
Could not save the search criterion.

Category:
Other

Cause:
An internal error.

Action:
Contact Oracle Support Services.

WCS-18021
Could not fetch the search criterion.

Category:
Other

Cause:
An internal error.

Action:
Contact Oracle Support Services.

WCS-18022
Could not fetch the sort criteria.

Category:
Other

Cause:
An internal error.

Action:
Contact Oracle Support Services.

WCS-18023
Could not save the sort criteria.

Category:
Other

Cause:
An internal error.

Action:
Contact Oracle Support Services.

WCS-18024
Cannot get an instance of the identity store

Category:
Other

Cause:
There was either an improper configuration or an internal error.

Action:
Contact Oracle Support Services.

WCS-18025
Could not create the contacts list.

Category:
Other

Cause:
An internal error.

Action:
Contact Oracle Support Services.

WCS-18026
Could not perform a people search.

Category:
Other

Cause:
An internal error.

Action:
Contact Oracle Support Services.

WCS-18401
An unexpected error occurred in the Message Board sub-system.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18402
Failed to create an instance of Message Board

Category:
Other

Cause:
Message Board viewing user name not found

Action:
Make sure that the user is logged in

WCS-18403
Failed to create an instance of Message Board

Category:
Other

Cause:
Message Board owner user name not specified

Action:
Provide owner user name in the request for an instance of Message Board

WCS-18405
Failed to publish Message Board activity

Category:
Other

Cause:
Activity Stream service raised an exception

Action:
Verify the reason for the failure in the Activity Stream sub-system

WCS-18406
Message Board message cannot be deleted

Category:
Other

Cause:
User is not authorized to delete this message

Action:
Resubmit the request with correct parameters

WCS-18407
Failed to delete Message Board message

Category:
Other

Cause:
Message does not exist

Action:
Resubmit the request with correct parameters

WCS-18408
Message Board message cannot be updated

Category:
Other

Cause:
User is not authorized to update this message

Action:
Resubmit the request with correct parameters

WCS-18409
Failed to update Message Board message

Category:
Other

Cause:
Message does not exist

Action:
Resubmit the request with correct parameters

WCS-18410
Message Board message cannot be added

Category:
Other

Cause:
Message content is empty

Action:
Provide a non empty message board message text

WCS-18411
Message Board message cannot be hidden

Category:
Other

Cause:
User is not authorized to hide message

Action:
Resubmit the request with correct parameters

WCS-18412
Failed to hide Message Board message

Category:
Other

Cause:
Message does not exist

Action:
Resubmit the request with correct parameters

WCS-18413
Failed to retrieve user display name from profile service

Category:
Other

Cause:

Action:

WCS-18414
Failed to add message to Message Board.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18415
Failed to hide or unhide message in Message Board.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18416
Failed to delete message in Message Board.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18417
Failed to query messages in Message Board.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18418
Failed to update message in Message Board.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18419
Failed to create an instance of Message Board.

Category:
Other

Cause:
Message Board preferences manager not specified

Action:
Provide preferences manager in the request for Message Board

WCS-18420
Failed to query preferences for Message Board.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18421
Message cannot be added to Message Board.

Category:
Other

Cause:
User is not authorized to add message

Action:
Resubmit the request with correct parameters

WCS-18422
Failed to retrieve Message Board message

Category:
Other

Cause:
Message does not exist

Action:
Resubmit the request with correct parameters

WCS-18423
Failed to find the portal of the message board.

Category:
Other

Cause:
The portal doesn't exist.

Action:
Contact your administrator.

WCS-18424
Failed to find the user of the message board.

Category:
Other

Cause:
The user doesn't exist.

Action:
Contact your administrator.

WCS-18425
Failed to attach file to selected portal.

Category:
Other

Cause:
The portal does not exist or does not have document services configured.

Action:
Contact your administrator.

WCS-18451
Unexpected error getting preference.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18452
Unexpected error saving preference.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18453
Encountered exception: {0}. For diagnosis, turn on the logging level to FINEST and retry the operation. Details about the current state: {1}.

Category:
Other

Cause:
An unexpected error occurred.

Action:
To diagnose the error, turn on the logging level to FINEST and retry the operation.

WCS-18501
Error retrieving {0}"s Profile

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18502
User: {0} not found in identity store.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Check if the specified user exists in the configured identity store and contact Oracle Support Services.

WCS-18503
Personal status note can be changed only for the current user

Category:
Other

Cause:
attempt made by an user to update personal status of another user

Action:
login as the user whose status you want to change

WCS-18504
unexpected error operating on personal status note

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18506
User does not have the privilege required to access the user profile.

Category:
Other

Cause:
Either the system policy or the target user's access control settings restrict the current user from performing this operation.

Action:
Contact the Administrator to grant the required permission, or contact the target user to allow access.

WCS-18507
Insufficient Privilege.

Category:
Other

Cause:
Cannot Edit Profile.

Action:
Contact Webcenter Administrator.

WCS-18508
Unexpected error retrieving user {0}''s photo

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18509
Unexpected error saving user {0}''s photo to the back-end. The photo may not have been saved. Please refresh to find out and then retry the operation.

Category:
Other

Cause:
An unexpected error occurred.

Action:
The photo may not have been saved. Please refresh to find out and then retry the operation. If the issue persists contact Oracle Support Services.

WCS-18510
Unexpected error invalidating user {0}''s photo cache

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18511
User not specified

Category:
Other

Cause:
The supplied username was null or blank.

Action:
Specify a valid username that is not null or blank.

WCS-18514
Unexpected error saving the Profile Admin Settings

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18515
Unexpected error saving the Profile user preference

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18516
Unexpected error initializing the admin config bean

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18517
Unexpected error saving the profile

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18520
Unexpected error retrieving unique identifier for user {0}"s photo

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18521
Unexpected error evaluating property "{0}" of base {1}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18522
Modifying property "{0}" of base {1} not allowed

Category:
Other

Cause:
The application does not allow modifying the value of the specified property of the specified base object.

Action:
Ensure that property of the object being modified is not read-only.

WCS-18523
Error getting the instant message address for the person

Category:
Other

Cause:
unexpected error getting the sip address

Action:
contact the administrator

WCS-18524
Error getting tag data

Category:
Other

Cause:
unexpected error getting tag data

Action:
contact the administrator

WCS-18525
Unexpected error saving attribute: {0}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with the error on the log.

WCS-18526
User does not have the privilege required for updating the user profile

Category:
Other

Cause:
The system policy restricts the current user from updating the user profile.

Action:
Contact the Administrator to obtain the required permission.

WCS-18527
The image file {0} you tried to upload was invalid. Provide a valid image file.

Category:
Other

Cause:
Unable to upload the image as the file is null or invalid.

Action:
Upload a valid image file

WCS-18528
Unexpected error instantiating object.

Category:
Other

Cause:
Unexpected error instantiating object.

Action:
contact the administrator

WCS-18529
Error instantiating profile (user name: {0}, GUID: {1})

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18530
Unable to retrieve display name for profile (user name: {0}, GUID: {1}) in locale {2}. For diagnosis, turn on the logging level to FINEST and retry the operation. Error summary: {3}.

Category:
Other

Cause:
An unexpected error occurred.

Action:
To diagnose the error, turn on the logging level to FINEST and retry the operation.

WCS-18531
Error navigating the hierarchy

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18532
Unexpected error writing vcard

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18533
Unexpected error retrieving reporting chain

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18534
Unexpected error searching user profiles

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18535
User: {0} not found in identity store or user does not have the required privilege for updating the user profile.

Category:
Other

Cause:
Either user is not available in the user repository or system policy restriction is applied.

Action:
contact the administrator

WCS-18536
User Class type not expected, found: {0} expected{1}.

Category:
Other

Cause:
The User instance found in the cache is not of the expected Class type.

Action:
Check if the Profile Service Lifecycle Listener is executed which sets the appropriate UserFactory.

WCS-18537
Error updating {0} with {1} and {2}.

Category:
Other

Cause:
The cause of this error could be MetadataNotFoundException, UnsupportedUpdateException, MDSIOException, ConcurrentMOChangeException or ValidationException

Action:
Check if the pages.xml is present, you have update permission on the document or if the pages.xml has some invalid content. If all the things listed are fine then try again after sometime.

WCS-18538
An unknown error occurred while trying to determine security attributes of type {0}

Category:
Other

Cause:
Review the logs for the underlying exception

Action:
Take action based on the underlying exception. Rerun the crawl.

WCS-18539
An unknown error occurred while trying to determine security attributes of type {0} for user {1}

Category:
Other

Cause:
Review the logs for the underlying exception

Action:
Take action based on the underlying exception. Rerun the crawl.

WCS-18540
Unknown error accessing assets

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18541
Action {0} cannot be executed on asset type {1}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18542
You do not have privileges to perform {0} on {1}.

Category:
Other

Cause:
The user does not have permission to perform the action on the given asset or asset type.

Action:
Contact your administrator to give you privileges to perform the required action.

WCS-18543
Unknown error while determining if user can access asset manager in scope {0}.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-18544
Unknown error while determining if user can access {0} asset type in asset manager in scope {1}.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-18545
Unknown error while deleting assets permission for scope {0}.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-18546
Selected operation cannot be performed as the asset is already deleted, refresh the list using the refresh icon.

Category:
Security

Cause:
The asset on which the action is being performed does not exist.

Action:
Refresh the list using the Refresh icon.

WCS-18547
Unknown error while trying to delete a resource for scope {0}, resourceType {1}, resourceGUID {2} and backURL {3}.

Category:
Other

Cause:
An unexpected error occurred while trying to delete a resource.

Action:
Contact Oracle Support Services with logs.

WCS-18548
Unknown error while trying to toggle the visibility of a resource for scope {0}, resourceType {1} and resourceGUID {2}

Category:
Other

Cause:
An unexpected error occurred while trying to toggle the visibility of a resource.

Action:
Contact Oracle Support Services with logs.

WCS-18549
Unknown error while trying to get resources.

Category:
Other

Cause:
An unexpected error occurred while trying to get the resources from the resource query options.

Action:
Contact Oracle Support Services with logs.

WCS-18701
An unexpected error occurred in the Feedback sub-system.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18702
Failed to create an instance of Feedback

Category:
Other

Cause:
Feedback object's viewing user name not found

Action:
Make sure that the user is logged in

WCS-18703
Failed to create an instance of Feedback

Category:
Other

Cause:
Feedback object's user name not specified

Action:
Provide user name in the request for an instance of Feedback

WCS-18705
Failed to publish Feedback activity

Category:
Other

Cause:
Activity Stream service raised an exception

Action:
Verify the reason for the failure in the Activity Stream sub-system

WCS-18706
Feedback message cannot be deleted

Category:
Other

Cause:
User is not authorized to delete this message

Action:
Resubmit the request with correct parameters

WCS-18707
Failed to delete Feedback message

Category:
Other

Cause:
Message does not exist

Action:
Resubmit the request with correct parameters

WCS-18708
Feedback message cannot be updated

Category:
Other

Cause:
User is not authorized to update this message

Action:
Resubmit the request with correct parameters

WCS-18709
Failed to update Feedback message

Category:
Other

Cause:
Message does not exist

Action:
Resubmit the request with correct parameters

WCS-18710
Feedback message cannot be added

Category:
Other

Cause:
User is not authorized to add message

Action:
Resubmit the request with correct parameters

WCS-18711
Feedback message cannot be hidden

Category:
Other

Cause:
User is not authorized to hide message

Action:
Resubmit the request with correct parameters

WCS-18712
Failed to hide Feedback message

Category:
Other

Cause:
Message does not exist

Action:
Resubmit the request with correct parameters

WCS-18713
Feedback message cannot be added

Category:
Other

Cause:
Feedback message content is empty

Action:
Provide a non empty feedback message text

WCS-18714
Failed to retrieve user display name from profile service

Category:
Other

Cause:

Action:

WCS-18715
Failed to add feedback.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18716
Failed to hide or unhide feedback.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18717
Failed to delete feedback.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18718
Failed to query feedback messages.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18719
Failed to create an instance of Feedback

Category:
Other

Cause:
Feedback object's preferences manager not specified

Action:
Provide preferences manager in the request for an instance of Feedback

WCS-18720
Failed to query preferences for Feedback object.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-18751
Unknown error accessing portal assets

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18752
Unknown error in instantiating portal assets factory

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18753
Unexpected error occurred while adding a portal asset.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18754
Unexpected error occurred while deleting a portal asset

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18755
Unexpected error occurred while updating a portal asset

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18756
Unexpected error occurred while getting the list of portal assets

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18757
Portal asset for update is not valid

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18758
An attribute in this asset is not valid.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18759
An error occurred in setting up the asset

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18760
Copy operation resulted in error. If you see the asset in asset manager, delete it.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18761
Delete operation resulted in error. If you see the asset in asset manager, try deleting it again.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18762
You do not have the privileges required to perform this operation.

Category:
Other

Cause:
No privilege to do the current operation

Action:
Contact webcenter administrator for change in role.

WCS-18763
Asset with the same display name already exists.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Enter a new display name for the asset.

WCS-18764
An unexpected error occurred while trying to check {0} access for {1}, denying access.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-18765
Unable to import, as the asset being imported conflicts with another asset.

Category:
Other

Cause:
Another asset in the target has the metadata file or jspx with the same path as the asset being imported.

Action:
Take action based on the underlying exception details.

WCS-18766
Unable to import as the asset being imported conflicts with another asset of a different type in the same portal.

Category:
Other

Cause:
Either the metadata file or jspx with the same path already exists on the target application in same scope.

Action:
Take action based on the underlying exception details.

WCS-18767
Unable to validate the content of the archive. Import of asset is aborted.

Category:
Other

Cause:
Error while trying to check if a document exists in MDS.

Action:
Take action based on the underlying exception details.

WCS-18768
Unable to import as {1}, as the asset in the archive is of type {0}

Category:
Other

Cause:
Select the correct asset type to import.

Action:
Select the correct asset type to import.

WCS-18769
Encountered exception while trying to determine if path {0} points to an asset, resorting to default security check.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-18770
Asset with id "{0}" does not exist.

Category:
Other

Cause:
The asset was possibly deleted by another user.

Action:
Refresh the asset manager to see if the asset still exists

WCS-18771
Unable to export as the asset is type {0} but was invoked as {1}

Category:
Other

Cause:
Incorrect asset type

Action:
Select the correct asset type to import.

WCS-18772
Unable to upload as the asset belongs to {0} but is being uploaded into {1}

Category:
Other

Cause:
The asset you are trying to upload belongs to a different portal.

Action:
Verify which portal owns the asset and then upload the asset to that portal.

WCS-18773
Unable to upload the asset. The owner of the asset is not valid.

Category:
Other

Cause:
Cannot identify the owner of the asset.

Action:
The archive is corrupt with invalid documents. Contact Oracle Support Services and provide log information.

WCS-18774
Global asset of type "{2}", with ID "{0}" does not exist.

Category:
Other

Cause:
The specified asset was probably deleted by another user.

Action:
Refresh the list of assets to see if the asset still exists.

WCS-18775
Asset of type "{2}", with ID "{0}" does not exist in the portal "{1}".

Category:
Other

Cause:
The specified asset was probably deleted by another user.

Action:
Refresh the list of assets to see if the asset still exists.

WCS-18776
You do not have the permissions required to perform the operation. Verify that you have the appropriate Create/Edit/Delete permission for the type of shared asset you are attempting to upload/download.

Category:
Other

Cause:
Verify that you have the appropriate Create/Edit/Delete permission.

Action:
Contact your WebCenter Portal administrator to request the required permissions.

WCS-18777
You do not have the permissions required to perform the operation. Verify that you have the appropriate Create/Edit/Delete permission for all portal assets or for the specific type of portal asset you are attempting to upload/download.

Category:
Other

Cause:
Verify that you have the appropriate Create/Edit/Delete asset permissions for the portal.

Action:
Contact the portal administrator to request the required permissions.

WCS-18778
Unable to upload as the archive does not contain a shared asset.

Category:
Other

Cause:
The asset you are trying to upload belongs to a specific portal, it is not a shared asset.

Action:
Verify which portal owns the asset and then upload the asset to that portal.

WCS-18779
Unable to upload the asset as the archive does not contain an asset that belongs to this portal.

Category:
Other

Cause:
The asset you are trying to upload belongs to a different portal.

Action:
Verify which portal owns the asset and then upload the asset to that portal.

WCS-18780
Global asset of type "{2}", with name "{0}" does not exist.

Category:
Other

Cause:
The specified asset was probably deleted by another user.

Action:
Refresh the list of assets to see if the asset still exists.

WCS-18781
Asset of type "{2}", with name "{0}" does not exist in the portal "{1}".

Category:
Other

Cause:
The specified asset was probably deleted by another user.

Action:
Refresh the list of assets to see if the asset still exists.

WCS-18782
Name or Resource Id of the resource to be exported is not specified. Specify either the name or the Id of the resource.

Category:
Other

Cause:
Name or ID of the resource to be exported in not mentioned.

Action:
Specify either the name or the ID of the resource.

WCS-18783
Name, Resource Id and type of the resource to be exported do not match.

Category:
Other

Cause:
Name, Resource Id and type of the resource to be exported do not match.

Action:
Specify either the name or the ID of the resource.

WCS-18784
Asset is a system asset. You cannot export system assets.

Category:
Other

Cause:
The asset you are trying to export is a system asset.

Action:
Refer to export documentation for more information or contact your administrator.

WCS-18785
Asset is a system asset. You cannot import system assets.

Category:
Other

Cause:
The asset you are trying to import is a system asset.

Action:
Refer to import documentation for more information or contact your administrator.

WCS-18786
Global asset of type "{3}", with the name "{0}" already exists with a different guid "{2}".

Category:
Other

Cause:
An unexpected error occurred.

Action:
Enter a new display name for the global asset.

WCS-18787
Asset of type "{3}", with the name "{0}" already exists in the portal "{1}" with a different guid "{2}".

Category:
Other

Cause:
An unexpected error occurred.

Action:
Enter a new display name for the asset.

WCS-18788
Asset of type "{1}", with id "{0}" is a system asset. You cannot export system assets.

Category:
Other

Cause:
The asset you are trying to export is a system asset.

Action:
Refer to export documentation for more information or contact your administrator.

WCS-18789
Asset of type "{1}", with name "{0}" is a system asset. You cannot export system assets.

Category:
Other

Cause:
The asset you are trying to export is a system asset.

Action:
Refer to export documentation for more information or contact your administrator.

WCS-18790
Portal asset for copy is not valid

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services with logs.

WCS-18791
The asset archive specified is not a valid asset archive.

Category:
Other

Cause:
The asset archive specified is not a valid asset archive.

Action:
Verify the asset archive and provide a valid archive.

WCS-18792
An exception occurred while exporting the data for the asset named "{0}" of type {1}.

Category:
Other

Cause:
An exception occurred while exporting the persistence data for the asset.

Action:
Verify the asset data in the persistence store and retry the operation.

WCS-18793
An exception occurred while importing the data for the asset named "{0}" of type {1}.

Category:
Other

Cause:
An exception occurred while importing the persistence data for the asset.

Action:
Verify the asset data in the persistence store and retry the operation.

WCS-18794
Error occurred while trying to find resource with id {0} and type {1}

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-18801
Access Policy for component "{0}" could not be saved.

Category:
Other

Cause:
There was an error in saving access policy.

Action:
Contact Oracle Support Services.

WCS-18802
Access Policy for component "{0}" defined by {1} could not be read.

Category:
Other

Cause:
There was an error in reading access policies of the component.

Action:
Verify in 'Display Options' tab that the el expression in 'Show Component' property is not malformed

WCS-18803
Attribute "{0}" could not be read for component "{1}"

Category:
Other

Cause:
There was an error in reading an attribute of the component.

Action:
Verify in 'Display Options' tab that the el expression in 'Show Component' property is not malformed

WCS-18804
Attribute "rendered" of component "{0}" having EL expression "{1}" could not be parsed.

Category:
Other

Cause:
There was an error in parsing EL Expression of attribute "rendered"

Action:
Verify in 'Display Options' tab that the el expression in 'Show Component' property is not malformed

WCS-18805
Attributes of component "{0}" has not been modified.

Category:
Other

Cause:
Attributes of selected component has not been modified.

Action:
Message is informational only

WCS-19001
Unexpected error occurred

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19002
Unable to execute operation on {0}

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19003
Metadata file {0} not found

Category:
Other

Cause:
The expected metadata file was not found

Action:
Contact Oracle Support Services

WCS-19004
Unexpected error occurred while creating page table

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19005
Internal error while creating policy store metadata for {0}

Category:
Other

Cause:
Policy store for WebCenter Portal not found

Action:
Contact Oracle Support Services

WCS-19007
Unable to copy application or portal policies for {0}

Category:
Other

Cause:
Exception occurred while copying policies for WebCenter Portal.

Action:
Contact Oracle Support Services.

WCS-19008
No matching users were found with search string {0}

Category:
Other

Cause:
No users matched the search string you entered: {0}

Action:
Enter a new search term and try again

WCS-19010
Couldn''t retrieve metadata for role {0}

Category:
Other

Cause:
No roles matched the search string you entered: {0}

Action:
Enter a new search term and try again.

WCS-19013
User not specified

Category:
Other

Cause:
A null or empty string was provided for the user name.

Action:
Enter a valid user name.

WCS-19014
Role not specified

Category:
Other

Cause:
A null or empty string was provided for the role name.

Action:
Enter a valid role name.

WCS-19016
Unable to grant user {2} with role {1} in {0}

Category:
Other

Cause:
An attempt to grant a user role failed. Either, role {1} does not exist, user {0} does not exist, or the user is already granted the role

Action:
Determine the cause and, if necessary, try again.

WCS-19017
Unable to revoke role {1} from identity {0}

Category:
Other

Cause:
An attempt to grant a identity role failed. Either, role {1} does not exist,identity {0} does not exist, or the identity does not have the specified role.

Action:
Determine the cause and, if necessary, try again.

WCS-19018
Unable to add role {0} to the policy store

Category:
Other

Cause:
An attempt to create a new role failed. Either the role already exists, or the policy store is currently unavailable

Action:
Determine the cause and, if necessary, try again.

WCS-19019
An error occurred while trying to remove role {0} from the policy store

Category:
Other

Cause:
An attempt to delete the specified role failed. Either the role does not exist, or the policy store is currently unavailable.

Action:
Determine the cause and, if necessary, try again.

WCS-19020
Identity {0} has already been granted the role(s).

Category:
Other

Cause:
User has been already granted the same role.

Action:
Determine the cause and, if necessary, try again.

WCS-19022
Role {0} already exists in the policy store

Category:
Other

Cause:
An attempt to create a new role failed because the policy store contains a role with the name specified.

Action:
Enter a unique name for the role.

WCS-19025
Only authenticated users can perform the requested operation

Category:
Other

Cause:
You do not have sufficient privileges to perform the requested operations.

Action:
Ask your WebCenter Portal administrator to grant you the appropriate privileges and then try again.

WCS-19026
Unable to revoke permission {0}

Category:
Other

Cause:
The specified permission was not removed from the policy store. The permission may not exist

Action:
Check whether the permission exists in the policy store

WCS-19027
Unable to grant permission {0}

Category:
Other

Cause:
The user was not granted the specified permission. The user may already be assigned that permission.

Action:
Check whether the user is assigned this permission.

WCS-19029
Policy for WebCenter Portal could not be found

Category:
Other

Cause:
Policy for WebCenter Portal was missing from the policy store.

Action:
Check the policy store for WebCenter Portal is configured correctly.

WCS-19030
Page definition for page {0} not found

Category:
Other

Cause:
Page definition for page {0} does not exist.

Action:
Check whether the page definition for page {0} exists

WCS-19031
Policy store instance cannot be null

Category:
Other

Cause:
No policy store instance was found

Action:
Verify and instantiate the policy store instance and try the operation again.

WCS-19032
Security Manager already initialized

Category:
Other

Cause:
An attempt was made to initialize the Security Manager but it was already initialized.

Action:
Use the existing Security Manager.

WCS-19033
Security Manager is not initialized

Category:
Other

Cause:
A security operation was attempted before the Security Manager was initialized.

Action:
Initialize the Security Manager and try again

WCS-19034
WebCenterSecurityManager class cannot be initialized directly

Category:
Other

Cause:
An attempt was made to initialize the WebCenterSecurityManager class through a protected constructor.

Action:
Initialize the WebCenterSecurityManager class with a default constructor.

WCS-19035
Security Manager is null

Category:
Other

Cause:
Security Manager could not be initialized

Action:
Use valid parameters and try again.

WCS-19036
Scoped Security Manager is null for scope {0}

Category:
Other

Cause:
Security manager can not be initialized

Action:
Please try to initialize again with proper parameters

WCS-19037
Invalid context {1} for scope {0}

Category:
Other

Cause:
Current scope did not match the cached scope

Action:
Refresh your page again and try again.

WCS-19038
An error occurred while importing security policies.

Category:
Other

Cause:
Failed to create security policies (grants, roles and permissions) during import.

Action:
Verify that the export archive is valid, otherwise check logs for error details and contact Oracle Support Services.

WCS-19039
ADFContext is NULL, so returning NULL as username

Category:
Other

Cause:
An internal error occurred while fetching the user name.

Action:
Contact Oracle Support Services.

WCS-19040
SecurityContext is NULL, so returning NULL as username

Category:
Other

Cause:
SecurityContext was not found for the current session

Action:
Contact Oracle Support Services.

WCS-19042
Unable to retrieve Personal Sidebar items

Category:
Other

Cause:
An error locating for opening the JSPX document for the Personal Sidebar

Action:
Ensure that the JSPX document pointing to the Personal Sidebar is available to the application

WCS-19043
Unable to persist personalization for tag with webcenterId "{0}" in the Personal Sidebar

Category:
Other

Cause:
An error saving the personalization document for the Personal Sidebar JSPX, or the tag with this webcenterId could not be located.

Action:
Ensure that the personalization is enabled on the Personal Sidebar JSPX, and the tag has a unique webcenterId

WCS-19044
Unable to retrieve item called {0} from the shell in the request {1}

Category:
Other

Cause:
Either the item name is incorrect or the item is not available in the current shell context

Action:
Verify that the item name is correct and that the shell context is setup properly for the current request.

WCS-19045
Unable to register shell handler of type {0}

Category:
Other

Cause:
Either the class name of the shell handler is incorrect or there was a problem while instantiating the shell handler

Action:
Verify whether the shell handler type is correct or determine why the shell handler is not instantiating properly

WCS-19046
Unable to retrieve the visibility of shell panel {0}

Category:
Other

Cause:
An error occurred trying to retrieve the visibility information from the shell handler of the current request.

Action:
Defaulting visibility to 'true'

WCS-19048
Unable to retrieve panel metadata for panel properties (panel name: {0})

Category:
Other

Cause:
The metadata for the panel in the shell metadata document may be corrupted or missing, or the name of the panel is incorrect.

Action:
Verify whether the panel name is correct and whether the metadata for the panel is valid

WCS-19049
An attempt to set change the skin was ignored

Category:
Other

Cause:
An attempt was made to change the skin but this feature is not yet implemented.

Action:
Contact Oracle Support Services.

WCS-19051
An attempt was made to set the template and ignored

Category:
Other

Cause:
This change would not take place as the feature is not implemented

Action:
Please contact Oracle Support for more details

WCS-19054
Error retrieving a physical page view-id for the request {0} (context URL {1})

Category:
Other

Cause:
The request URL could be invalid, or an unknown problem occurred fetching the metadata

Action:
Verify the request URL and try again.

WCS-19055
Unable to display a page for the requested URL {0}

Category:
Other

Cause:
The request URL was invalid, either because there was no shell handler or the shell handler could not provide a physical page to forward to.

Action:
Verify the request URL and try again.

WCS-19058
Unable to retrieve scope IDs for the current user

Category:
Other

Cause:
An internal error occurred while fetching the scope for the current user.

Action:
Contact Oracle Support Services

WCS-19061
Unable to INSTANTIATE shell handler factory of type {0}

Category:
Other

Cause:
Shell handler factory of type {0} was not in the classpath.

Action:
Contact Oracle Support Services

WCS-19062
Unable to INITIALIZE the shell handler factory

Category:
Other

Cause:
An internal error occurred while initializing the shell handler factory.

Action:
Contact Oracle Support Services.

WCS-19066
Unable to set up the default shell handler factory.

Category:
Other

Cause:
An internal error occurred while setting up the default shell handler factory.

Action:
Contact Oracle Support Services.

WCS-19067
Unable to navigate to the page. Page creation might have failed or an error occurred while attempting to load the new page. Open your Manage Pages dialog box to see if the page exists. If the problem persists, contact your administrator.

Category:
Other

Cause:
An error occurred trying to reference the newly created page (the page may not have been created properly).

Action:
Try to selecting the new page from the pages dropdown list. If the page is not listed, try creating the page again

WCS-19068
Unable to create page in the current scope

Category:
Other

Cause:
An unexpected error occurred while trying to create a page in a scope.

Action:
Ask your WebCenter Portal administrator to resolve the issue.

WCS-19070
Unable to delete page {0} ({1})

Category:
Other

Cause:
An attempt to delete a page failed. Either the page and/or its associated files (for example, ADFm page definition) have been modified but not saved

Action:
Verify that the page is not being modified and try again.

WCS-19071
Page {0} ({1}) not deleted properly. Unable to remove associated metadata.

Category:
Other

Cause:
An attempt was made to delete a page when metadata associated with the page was in use.

Action:
Try again.

WCS-19072
Unable to retrieve the list of users

Category:
Other

Cause:
An attempt to retrieve the user list failed.Either the Identity store was corrupt or is inaccessible.

Action:
Verify that the identity store is valid and accessible, and try again.

WCS-19073
Unable to register page {0} (of scope {1}) for navigation

Category:
Other

Cause:
An error occurred while registering the page {0}.

Action:
Try to register the page again and if unsuccessful contact Oracle Support.

WCS-19075
No users available

Category:
Other

Cause:
No users found in the identity store associated with WebCenter Portal.

Action:
Contact Oracle Support Services.

WCS-19077
Permission class {0} does not have proper constructor method

Category:
Other

Cause:
The specified class does not have the required constructor

Action:
Provide the required constructor in the specified class

WCS-19079
Unable to process the security extension metadata

Category:
Other

Cause:
The argument is not an instance of ExtensionPermissionMetadata

Action:
Provide an instance of ExtensionPermissionMetadata as the argument

WCS-19080
Unable to access permission class {0} in your project libraries

Category:
Other

Cause:
Either the specified permission class does not exist or it is not in the correct location.

Action:
Ensure that the specified permission class is in the correct location.

WCS-19082
Unable to load up the {0} service.

Category:
Other

Cause:
An internal error occurred and the {0} service failed to load.

Action:
Contact Oracle Support Services

WCS-19083
Access to permission class {0} is not allowed

Category:
Other

Cause:
An attempt was made to access the specified permission class.Permission class {0} is not accessible.

Action:
Contact Oracle Support Services

WCS-19084
Permission class{0} can not be instantiated

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19085
Unable to instantiate the policy store for WebCenter Portal

Category:
Other

Cause:
An error occurred while trying to access the policy store associated with WebCenter Portal.

Action:
Contact Oracle Support Services

WCS-19088
Failed to register application management beans

Category:
Other

Cause:
Application management beans(MBean) registration failed.Either there are issues with OC4J or the application was not packaged properly.

Action:
Restart OC4J or examine OC4J log files for further details.

WCS-19089
Failed to unregister application management beans

Category:
Other

Cause:
Application management beans(MBean) unregistration failed. Either the Mbeans were not registered or the Mbeans were already unregistered.

Action:
Examine the OC4J log files for further details.

WCS-19090
An unexpected error has occurred, unable to complete the export process.

Category:
Other

Cause:
The export process failed due to an internal error.

Action:
Contact Oracle Support Services.

WCS-19101
Unable to save the export archive on the local file system due to an unexpected error.

Category:
Other

Cause:
Unexpected error occurred while saving the export archive on the local file system.

Action:
Contact Oracle Support Services

WCS-19102
Unexpected error occurred while exporting the security policy. Unable to export the policy store.

Category:
Other

Cause:
An unexpected error occurred while exporting policy store metadata to the local file system.

Action:
Contact Oracle Support Services.

WCS-19104
Unable to export connection details for external application with ID {0}

Category:
Other

Cause:
An internal error occurred. Unable to retrieve details for an external application appearing in WebCenter Portal.

Action:
Ask your WebCenter Portal administrator to clean up external applications appearing in the Sidebar or reconfigure the external application connection using Enterprise Manager.

WCS-19105
Unable to find connection details for external application with ID {0}

Category:
Other

Cause:
No connection details found for external application with the specified ID.

Action:
Remove the external application link associated with the specified ID from the Applications pane in the Sidebar.

WCS-19106
Unable to save preference settings

Category:
Other

Cause:
An error occurred while attempting to save preferences settings to the metadata store.

Action:
Contact Oracle Support Services.

WCS-19107
Invalid date format {0} retrieved from the preference store.

Category:
Other

Cause:
An attempt was made to retrieve date information but the source date format was invalid.

Action:
Verify whether the date format source returns the correct date format.

WCS-19108
Invalid time format {0} retrieved from the preference store.

Category:
Other

Cause:
An attempt was made to retrieve time information but the source time format was invalid.

Action:
Verify whether the time format source returns the correct time format

WCS-19109
Unable to find service.

Category:
Other

Cause:
Unable to find the service metadata in WebCenter Portal

Action:
Contact Oracle Support Services

WCS-19110
Specify a location on server.

Category:
Other

Cause:
Unable to locate archive for import.

Action:
Specify the archive's name and server location, and try again.

WCS-19111
Specify an archive that exists on the file system.

Category:
Other

Cause:
Unable to locate archive for import.

Action:
Specify a valid archive that exists on the file system and try again.

WCS-19112
Specify a server location.

Category:
Other

Cause:
Unable to locate the specified directory for the export archive.

Action:
Specify a valid directory on the server for the export archive and try again.

WCS-19113
Specify an existing directory on the server.

Category:
Other

Cause:
Unable to locate the specified directory.

Action:
Specify a valid directory on the server and try again.

WCS-19114
Specify a valid name for the portal archive. Usage of special character / or \ is not allowed.

Category:
Other

Cause:
Usage of special character / or \ is not allowed.

Action:
Specify a valid name for the portal archive.

WCS-19115
Specify a valid name for the portal template archive. Usage of special character / or \ is not allowed.

Category:
Other

Cause:
Usage of special character / or \ is not allowed.

Action:
Specify a valid name for the portal template archive.

WCS-19116
Specify a valid name for the portal archive with the file extension {0}.

Category:
Other

Cause:
Invalid file extension specified.

Action:
Specify a valid name for the portal archive with the file extension '.par'

WCS-19117
Specify a valid name for the portal template archive with the file extension {0}.

Category:
Other

Cause:
Invalid file extension specified.

Action:
Specify a valid name for the portal template archive with the file extension '.par'

WCS-19118
Invalid portal archive extension provided: {0}. Specify a valid name for the portal archive and use the file extension {1}.

Category:
Other

Cause:
Invalid portal archive extension specified.

Action:
Specify a valid name for the portal archive and use the file extension '.par'

WCS-19119
Unable to add the new link : {0}

Category:
Other

Cause:
An attempt to add a new link {0} to the metadata store failed.

Action:
Contact Oracle Support Services.

WCS-19120
Unable to add link as no proper handler found for the selected resource type

Category:
Other

Cause:
An attempt to add a new link but the resource being added is neither a task flow or an external application.

Action:
Only task flows or external application link can be included.

WCS-19121
Unable to retrieve the shell configuration metadata

Category:
Other

Cause:
The metadata file is corrupt or missing.

Action:
Ensure that the file exists and complies with the schema.Alternatively, contact your WebCenter Portal administrator for assistance.

WCS-19122
Invalid shell panel name

Category:
Other

Cause:
The shell panel name was probably NULL.

Action:
Provide a valid shell panel name.

WCS-19123
Unable to retrieve the shell handler for the current request {1}

Category:
Other

Cause:
The shell handler was not set for the current request

Action:
Verify the URL and that the WebCenter Portal shell filter is configured to handle requests of this kind

WCS-19124
Unable to save changes to shell metadata

Category:
Other

Cause:
An error occurred while saving the shell metadata document.

Action:
Ensure that the shell metadata document is not corrupt and is writable and personalizable.

WCS-19125
Account for user {0} is disabled

Category:
Other

Cause:
The account for user {0} account is disabled.

Action:
Ask the WebCenter Portal administrator to activate the account.

WCS-19126
Account for user {0} is inactive

Category:
Other

Cause:
The account for user {0} is disabled.

Action:
Ask the WebCenter Portal administrator to activate the account.

WCS-19127
The account for user {0} is locked

Category:
Other

Cause:
The account is locked for user {0}

Action:
Ask the WebCenter Portal administrator to unlock the account.

WCS-19128
Password has expired for user account {0}

Category:
Other

Cause:
Password for this user has expired

Action:
Contact the WebCenter Portal administrator for assistance.

WCS-19129
Incorrect Old Password for user account {0}

Category:
Other

Cause:
The old password specified for this user is not correct.

Action:
Enter the correct password

WCS-19130
Password for user account {0} is null

Category:
Other

Cause:
No password was specified.

Action:
Enter a valid password.

WCS-19131
Error occurred granting permissions to user {0} for the newly created page {1}

Category:
Other

Cause:
An unexpected error occurred while granting the user permission

Action:
Contact the WebCenter Portal administrator

WCS-19132
Unable to retrieve the permission target for page {0}

Category:
Other

Cause:
An unexpected error occurred. The ADFm page definition of the page may be missing

Action:
Ensure that the page definition exists and is valid.

WCS-19133
Unable to determine the page in focus

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services

WCS-19134
Unable to hide a page, locked by another user

Category:
Other

Cause:
An attempt was made to hide a page that is currently locked by another user.

Action:
Contact Oracle Support Services.

WCS-19135
No page selected for hiding

Category:
Other

Cause:
Unable to determine which page has focus.

Action:
Select the page you want to hide and try again.

WCS-19136
Unable to hide the page.

Category:
Other

Cause:
An attempt was made to hide the last open page.

Action:
Open some other page and try again.

WCS-19137
Unable to determine the page focus for hiding

Category:
Other

Cause:
Unable to determine which page has focus.

Action:
Select the page you want to hide and try again. Alternatively, contact Oracle Support Services.

WCS-19138
Unable to encode the value {1} of parameter {0} using encoding format {2}

Category:
Other

Cause:
The encoding format was unexpectedly invalid.

Action:
Contact Oracle Support Services.

WCS-19139
Unable to decode the value {1} of parameter {0} using encoding format {2}

Category:
Other

Cause:
The encoding format was unexpectedly invalid.

Action:
Contact Oracle Support Services.

WCS-19140
Unable to update the page titled {0} ({1})

Category:
Other

Cause:
An error occurred while saving the changes.

Action:
Contact Oracle Support Services.

WCS-19141
Unable to save changes to the metadata store

Category:
Other

Cause:
An error occurred while saving the changes.

Action:
Contact Oracle Support Services.

WCS-19142
Role mapping SPIs are throwing exception

Category:
Other

Cause:
An internal occurred error while accessing role mapping SPIs.

Action:
Contact Oracle Support Services.

WCS-19143
Unable to retrieve the catalog for adding applications

Category:
Other

Cause:
An attempt to access the external application catalog failed. Either the external application catalog is not configured or configuration details are unavailable.

Action:
Check whether the ext-app-catalog attribute is configured in webcenter-config.xml

WCS-19144
Role name for user account is null or contains invalid characters

Category:
Other

Cause:
Either the role name was left blank or the role name contained invalid characters.

Action:
Enter a valid role name.

WCS-19145
Operation succeeded with errors. The mapping of roles failed

Category:
Other

Cause:
Changes in services failed due to the following errors

Action:
Contact Oracle Support Services.

WCS-19146
Grant role completed with errors The mapping of roles failed in scope {0}

Category:
Other

Cause:
Changes in services failed due to the following errors

Action:
Contact Oracle Support Services.

WCS-19147
Page path can not be null

Category:
Other

Cause:
The specified page path is null or an empty string.

Action:
Provide a valid string for the page path.

WCS-19148
Cannot get the service categories metadata from the application metadata

Category:
Other

Cause:
Service category metadata has not been defined in the application metadata

Action:
Contact Oracle Support Services.

WCS-19149
Cannot get metadata for all services from the application metadata.

Category:
Other

Cause:
All service metadata has not been defined in the application metadata.

Action:
Contact Oracle Support Services.

WCS-19150
Cannot get metadata for configurable services from the application metadata

Category:
Other

Cause:
Metadata for configurable services has not been defined in the application metadata.

Action:
Contact Oracle Support Services.

WCS-19151
Cannot find a service with the ID {0}

Category:
Other

Cause:
No definition exists for a service with the specified service identifier

Action:
Contact Oracle Support Services.

WCS-19152
User {0} already has access.

Category:
Other

Cause:

Action:

WCS-19153
Edit the user to modify his role.

Category:
Other

Cause:

Action:

WCS-19154
This exception is due to one or more of the following exceptions -

Category:
Other

Cause:
One or more services configurations have failed.

Action:
Contact Oracle Support Services.

WCS-19155
User {0} already has access or is invited.

Category:
Other

Cause:

Action:

WCS-19156
You cannot send an invite to this user as an invite has already been sent.

Category:
Other

Cause:

Action:

WCS-19157
Portal {0} may have been deleted or renamed

Category:
Other

Cause:
An attempt was made to access a portal that has been deleted or renamed.

Action:
Contact the portal moderator or try searching for the portals.

WCS-19158
Cannot personalize visibility of page {0} in portal {1}

Category:
Other

Cause:
A personalization attempt failed. Either the backing store could not be accessed or some other personalization operation was performed simultaneously.

Action:
Try the operation again. If the problem persists, contact your WebCenter Portal administrator.

WCS-19159
Unable to save page creation

Category:
Other

Cause:
An attempt to save the new page failed. Either the back-end store could not be accessed or another page was created simultaneously.

Action:
Try the operation again. If the problem persists, contact your WebCenter Portal administrator.

WCS-19160
Unable to save the personal sequence of pages in scope {0}

Category:
Other

Cause:
An attempt to personalize the page sequence failed. Either the back-end store could not be accessed or some other personalization operation was performed simultaneously

Action:
Try the operation again. If the problem persists, contact your WebCenter Portal administrator.

WCS-19161
Unable to save the change in sequence of pages in scope {0}

Category:
Other

Cause:
An attempt to change page sequence failed. Either the back-end store could not be accessed or a similar operation was performed simultaneously.

Action:
Try the operation again. If the problem persists, contact your WebCenter Portal administrator.

WCS-19162
Revoke role completed with errors The mapping of roles failed

Category:
Other

Cause:
Changes in services failed due to the following errors

Action:
Contact Oracle Support Services

WCS-19163
Scope is NULL for Security Manager

Category:
Other

Cause:
Scope identifier passed to the security manager is NULL.

Action:
Contact Oracle Support Services.

WCS-19164
The security policy in the archive file was found to be invalid.

Category:
Other

Cause:
The imported security policy file was found to be invalid.

Action:
Export the data again and try the import operation again.

WCS-19165
The security policy in the archive file to be imported is invalid as it contains more than one jazn-policy node.

Category:
Other

Cause:
The imported security policy file is invalid as it contains more than one jazn-policy node.

Action:
Export the data again the import operation again.

WCS-19166
The security policy in the archive file to be imported is located on a read-only file system and this means the data cannot be updated.

Category:
Other

Cause:
The imported security policy file is located on a read-only file system and this means the data cannot be updated.

Action:
Export the data again and try the import operation again.

WCS-19167
Failed to import security configuration from the selected archive.

Category:
Other

Cause:
An unexpected error occurred while updating the deployed application in the import source archive.

Action:
Check the logs for details of the error.Alternatively, contact Oracle Support Services.

WCS-19168
Role {0} is created successfully but failed to copy the permissions from role {1}. The role {1} is not found.

Category:
Other

Cause:
An attempt to create the role failed because the base role was not found.

Action:
Check whether the base role is still available.

WCS-19169
An error occurred while trying to remove a role {0} from the policy store.

Category:
Other

Cause:
The specified role does not exist in the policy store.

Action:
Check the details of the error and try again.

WCS-19170
Application role {0} still used in the policy store

Category:
Other

Cause:
The specified role is in use.

Action:
Remove the usage of the role and try again.

WCS-19171
Application role {0} to be granted is not found

Category:
Other

Cause:
Specified role was not found.

Action:
Check the role name {0} and try again.

WCS-19172
Internal error while creating security manager for portal {0}

Category:
Other

Cause:
Unable to resolve the Scope GUID for Scope {0}

Action:
Contact Oracle Support Services.

WCS-19173
New passwords for user account {0} do not match

Category:
Other

Cause:
Passwords were entered incorrectly.

Action:
Enter the correct passwords.

WCS-19174
Few of the mandatory resource(s) are in use. Please try again later.

Category:
Other

Cause:
The lock, client is trying to release is already locked.

Action:
Try after some time

WCS-19175
Unable to release the lock on document {0}

Category:
Other

Cause:
A call to release lock in the back-end has failed.

Action:
Contact Oracle Support Services.

WCS-19176
Releasing the current lock on {0} failed

Category:
Other

Cause:
The lock, client is trying to release is already released.

Action:
Acquire the lock again to release.

WCS-19177
Name Cannot Be Null

Category:
Other

Cause:
Name Cannot Be Null

Action:
Enter a User or Group

WCS-19178
User Not Found

Category:
Other

Cause:
User Not Found

Action:
Enter a username

WCS-19179
Group not found or multiple groups with the same name exist.

Category:
Other

Cause:
Group not found or multiple groups with the same name exist

Action:
Enter a Group

WCS-19180
User with this name doesn't exist

Category:
Other

Cause:
User with this name doesn't exist

Action:
Enter a role which has users

WCS-19181
Unable to read the application configuration metadata

Category:
Other

Cause:
The metadata file could have got corrupt or removed

Action:
Please ensure that the file exists and complies with the schema, or contact the administrator for assistance

WCS-19182
Unable to move link/folder

Category:
Other

Cause:
The metadata file could have got corrupt or removed

Action:
Contact Oracle Support Services

WCS-19183
Unable to create folder {0}

Category:
Other

Cause:
The metadata file could have got corrupt or removed

Action:
Contact Oracle Support Services

WCS-19184
Unable to delete link/folder {0}

Category:
Other

Cause:
The metadata file could have got corrupt or removed

Action:
Contact Oracle Support Services

WCS-19185
Role cannot be created because it contains special characters

Category:
Other

Cause:
Creation of Role {0} failed because it contains special characters

Action:
Remove special characters used in your role and try again.

WCS-19186
Role {0} cannot be created, as the role of same name exists in the policy store

Category:
Other

Cause:
Creation of Role {0} failed because policy store already contains a role of same name

Action:
Try changing role name

WCS-19187
Granting of Role {0} partially succeeded for identity {1}. Granting permissions for {2} failed. You can take actions regarding these warnings in portal settings.

Category:
Other

Cause:
Granting of Role for certain Services failed due to RoleMapping Exception

Action:
Please check the log for actual error stack.

WCS-19188
Revoking of Role {0} partially succeeded for identity {1}. Revoking permissions for {2} failed. You can take actions regarding these warnings in portal settings.

Category:
Other

Cause:
revoking of Role for certain Services failed due to RoleMapping Exception

Action:
Please check the log for actual error stack.

WCS-19189
Mapping the permissions {0} failed. You may want to try the operation again after some time or can contact Administrator.

Category:
Other

Cause:
Granting of Role for certain Services failed due to RoleMapping Exception

Action:
Please check the log for actual error stack.

WCS-19190
Fatal Error while granting role for certain services.

Category:
Other

Cause:
Granting of Role for certain Services failed due to RoleMapping Exception

Action:
Please check the log for actual error stack.

WCS-19191
User(s) {0} has already been granted the role {1}.

Category:
Other

Cause:
Current User / Role {0} has been already granted the application role.

Action:
Don't Provision this user since it is already provisioned.

WCS-19192
Role has been granted with errors. You might want to contact Administrator or Remove/Grant Role again.

Category:
Other

Cause:
Role was granted with errors.

Action:
Contact the Administrator.

WCS-19193
Fatal Error while granting the role.

Category:
Other

Cause:
Fatal Error while granting the role.

Action:
Contact Administrator.

WCS-19194
Invitations were sent out but persisting the invited users data resulted in fatal error.

Category:
Other

Cause:
Members Fatal Error while granting the role.

Action:
Contact Administrator.

WCS-19195
Page {0} cannot be found in the system

Category:
Other

Cause:
The page may have been deleted or the page path is incorrect

Action:
Specify a correct path to an existing page

WCS-19196
{0} : Irresolvable error(s) occurred. You may want to contact Administrator with the error reference.

Category:
Other

Cause:
Fatal Error occurred.

Action:
Contacts the administrator.

WCS-19197
{0} : Unexpected error(s) occurred. You may want to contact Administrator with the error reference.

Category:
Other

Cause:
Fatal Error occurred.

Action:
Contacts the administrator.

WCS-19198
{0} : Unknown error(s) occurred. You may want to contact Administrator with the error reference.

Category:
Other

Cause:
Fatal Error occurred.

Action:
Contacts the administrator.

WCS-19199
{0} : Multiple errors occurred {1}

Category:
Other

Cause:
Fatal Error occurred.

Action:
Contacts the administrator.

WCS-19200
Fatal error while removing some grants. Please contact Administrator with error reference.

Category:
Other

Cause:
Fatal Error occurred.

Action:
Contacts the administrator.

WCS-19201
Fatal error while removing the role. Please contact Administrator with error reference.

Category:
Other

Cause:
Fatal Error occurred.

Action:
Contacts the administrator.

WCS-19202
Revoking role was partially successful. You can try this operation again after some time or contact Administrator.

Category:
Other

Cause:
Fatal Error occurred.

Action:
Contacts the administrator.

WCS-19203
Fatal error while creating the role. Please contact Administrator with error reference.

Category:
Other

Cause:
Fatal Error occurred.

Action:
Contacts the administrator.

WCS-19204
Unable to save Invite message for portal {0} due to unknown errors. Please try later or contact administrator

Category:
Other

Cause:
Error occurred while obtaining the invite message

Action:
Try later or contact administrator

WCS-19205
Unable to save member changes for a portal{0} due to unknown errors. Please try later or contact administrator

Category:
Other

Cause:
Error occurred while saving the member changes

Action:
Try later or contact administrator

WCS-19206
Could not find security policy in the archive file being imported.

Category:
Other

Cause:
The security policy file was not found in import archive.

Action:
Export the data again and try the import operation again.

WCS-19207
One or more mandatory roles are not found in the copied instance for scope {0}. Role Name: {1}

Category:
Other

Cause:
One or more mandatory roles are not found in the copied instance.

Action:
Add the mandatory role {1} in the security metadata to get WebCenter Portal functionality or contact administrator.

WCS-19208
Deletion of security metadata failed for scope {0}

Category:
Other

Cause:
Deletion of roles for the current scope {0} has failed.

Action:
Try later or contact administrator.

WCS-19209
An unexpected error occurred while trying to upload WebCenter Portal logo to path {0}

Category:
Other

Cause:
MDS StreamedObject creation failed for WebCenter Portal logo

Action:
Contact administrator for further assistance.

WCS-19210
The image upload failed as the image file you tried to upload was invalid. Provide a valid image file.

Category:
Other

Cause:
Unable to upload the WebCenter Portal logo as the file is null or not available.

Action:
Upload a valid image file

WCS-19211
An error occurred while trying to retrieve the templates to be used for page creation. Please contact Administrator with error reference.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contacts the administrator.

WCS-19212
An error occurred while trying to determine the template selected for page creation. Please contact Administrator with error reference.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contacts the administrator.

WCS-19213
Unable to persist customization for tag with webcenterId "{0}" in the Personal Sidebar

Category:
Other

Cause:
An error saving customizations on the Personal Sidebar JSPX, or the tag with this webcenterId could not be located.

Action:
Ensure that the customization is enabled on the Personal Sidebar JSPX, and the tag has a unique webcenterId

WCS-19214
Failed to get the custom page permission for pageDef {0} for action {1}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19215
Failed to get the roles having permission {0}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19216
Failed to get the users having permission {0}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19217
Unable to get list of links

Category:
Other

Cause:
An error occurred while getting the list.

Action:
Contact Oracle Support Services.

WCS-19218
An error occurred while saving the page default settings. The settings may not have been saved.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19219
Unexpected error occurred while deleting the page

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19220
Search for role {0} resulted in more than one result. Please contact Administrator to get it rectified

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19221
While provisioning the services, errors were encountered for following services - {0}. Check if these services have been configured correctly.

Category:
Other

Cause:
While copying the services, errors were encountered for certain services.

Action:
Contact administrator.

WCS-19222
Unknown error in adding link to the table

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19223
Unknown error in retrieving the link information

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19224
Unknown error in updating the link information

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19225
Unknown error in deleting the link

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19226
Unable to close connection

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19227
Unexpected error occurred while restoring the page

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19228
Unexpected error occurred while creating list of pages

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19229
Error occurred in getting the complete list of pages you can access. Please contact the administrator.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19230
Invalid page name

Category:
Other

Cause:
Invalid page name

Action:
Please enter a valid page name.

WCS-19231
Unexpected error occurred while creating the page

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19232
While provisioning the services, errors were encountered for following services - {0}. Check if these services have been configured correctly.

Category:
Other

Cause:
While provisioning the services, errors were encountered for certain services.

Action:
Contact administrator.

WCS-19233
While renaming all the provisioned services, errors were encountered for following services - {0}.

Category:
Other

Cause:
While renaming the portal, errors were encountered for certain services.

Action:
Contact administrator.

WCS-19234
While unprovisioning the services, errors were encountered for following services - {0}.

Category:
Other

Cause:
While unprovisioning the services, errors were encountered for certain services.

Action:
Contact administrator.

WCS-19235
Unknown error occurred. Please contact Administrator.

Category:
Other

Cause:
Unknown error occurred.

Action:
Contact administrator.

WCS-19236
The following service(s) are currently unavailable: {0}. If the problem persists contact your administrator.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19237
Unable to export the portal {0}. Either the portal does not exist or the portal is being exported/imported by another user. Refresh the portal list and try again.

Category:
Other

Cause:
Unable to acquire a lock on the scope of portal.

Action:
Refresh the portal list and try again. If the problem persists, contact the administrator.

WCS-19238
Unable to export the portal template {0}. Either the portal template does not exist or the portal template is being exported/imported by another user. Refresh the portal template list and try again.

Category:
Other

Cause:
Unable to acquire a lock on the scope of portal template.

Action:
Refresh the portal template list and try again. If the problem persists, contact the administrator.

WCS-19239
Unable to import portals as required resources are not available. Portals being replaced on the target either do not exist or are being exported/imported by another user. Refresh the portal list and try again.

Category:
Other

Cause:
Unable to acquire a global lock to prevent create, delete, rename or import operations on portals.

Action:
Wait for some time and try the import operation again. If the problem persists, contact the administrator.

WCS-19240
Unable to import portal templates as required resources are not available. Portal templates being replaced on the target either do not exist or are being exported/imported by another user. Refresh the portal template list and try again.

Category:
Other

Cause:
Unable to acquire a global lock to prevent create, delete, rename or import operations on portal templates.

Action:
Wait for some time and try the import operation again. If the problem persists, contact the administrator.

WCS-19241
Errors occurred in the page.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-19242
Unexpected error occurred while accessing copyright message.

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19243
Unexpected error occurred while accessing privacy URL.

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19244
Unexpected error occurred while accessing footer information.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19245
An error occurred while saving the page security settings. The settings may not have been saved.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-19246
Error occurred while refreshing the table of pages.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-19247
Modification of role operation not supported for scope {0}

Category:
Other

Cause:
Currently the modification of role not supported.

Action:
Contact the administrator.

WCS-19248
Portal {0} being exported is either online or being exported/imported by another user. Wait for some time and try the export operation again.

Category:
Other

Cause:
Portal is either online or blocked by another user/process.

Action:
Refresh the portal list and try to export the portal again. If the problem persists, contact the administrator.

WCS-19249
Portal template {0} you are trying to export is being exported/imported by another user. Wait for some time and try the export operation again.

Category:
Other

Cause:
Portal template is blocked by another user/process.

Action:
Refresh the portal template list and try to export the portal template again. If the problem persists, contact the administrator.

WCS-19250
Portal template {0} you are trying to import is being exported/imported by another user on the target. Wait for some time and try the import operation again.

Category:
Other

Cause:
Portal template is blocked by another user/process.

Action:
Wait for some time and try to import the portal template again. If the problem persists, contact the administrator.

WCS-19251
You are trying to import portals but the archive specified contains portal templates. Check the archive file and try again.

Category:
Other

Cause:
You are trying to import portals but the archive specified contains portal templates.

Action:
Use an export archive that contains portals.

WCS-19252
You are trying to import portal templates but the archive specified contains portals. Check the archive file and try again.

Category:
Other

Cause:
You are trying to import portal templates but the archive specified contains portals.

Action:
Use an export archive that contains portal templates.

WCS-19253
Cannot locate the document "{0}".

Category:
Other

Cause:
The path is incorrect or it is not available in the system.

Action:
Verify whether the path is correct and is available in the system.

WCS-19254
Error occurred while reading the WebCenter Portal environment configuration file {0}.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-19255
Unexpected error occurred while navigating to portal administration pages.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-19256
Error occurred while saving the folder.

Category:
Other

Cause:
An unexpected error occurred while saving the folder.

Action:
Contact the administrator.

WCS-19257
Unexpected error occurred while acquiring the write lock on the document {0}.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-19258
Error occurred while clearing the deleted/renamed portal page.

Category:
Other

Cause:
Error occurred while clearing the deleted/renamed portal page.

Action:
Error occurred while clearing the deleted/renamed portal page.

WCS-19259
Portal "{0}" on the target application is either online or being exported/imported by another user. Wait for some time and try the import operation again.

Category:
Other

Cause:
Portal either online or blocked by another user/process.

Action:
Wait for some time and try the import operation again. If the problem persists, contact the administrator.

WCS-19260
The current process could not be executed. Wait for some time and try again.

Category:
Other

Cause:
An unexpected error occurred while saving administration changes.

Action:
Contact system administrator.

WCS-19261
Error occurred while saving administration changes.

Category:
Other

Cause:
An unexpected error occurred while saving administration changes.

Action:
Contact system administrator.

WCS-19262
Another administrator is modifying the setting. Try again later.

Category:
Other

Cause:
An unexpected error occurred while saving administration changes.

Action:
Contact system administrator.

WCS-19263
Fatal error occurred while getting the roles for current scope.

Category:
Other

Cause:
An unexpected error occurred while getting the roles.

Action:
Please contact the administrator.

WCS-19264
Fatal error occurred while inviting user {0} for role {1}

Category:
Other

Cause:
An unexpected error occurred while getting the members.

Action:
Please contact the administrator.

WCS-19265
Fatal error occurred while getting members.

Category:
Other

Cause:
An unexpected error occurred while getting the members.

Action:
Please contact the administrator.

WCS-19266
Fatal error occurred while getting invitation message from the repository.

Category:
Other

Cause:
An unexpected error occurred while getting message.

Action:
Please contact the administrator.

WCS-19267
Error occurred while reading the list of tabs from persistence store.

Category:
Other

Cause:
An unexpected error occurred while reading the list of tabs.

Action:
Contact system administrator.

WCS-19268
Following error occurred while storing the list of tabs to persistence store - {0}

Category:
Other

Cause:
An unexpected error occurred while storing the list of tabs.

Action:
Contact system administrator.

WCS-19269
Error in processing the pages.

Category:
Other

Cause:
Unexpected error occurred while adding the page.

Action:
Contact Oracle Support Services.

WCS-19270
Error in processing the pages.

Category:
Other

Cause:
Unexpected error occurred while removing the page.

Action:
Contact Oracle Support Services.

WCS-19271
Error in processing the pages.

Category:
Other

Cause:
Unexpected error occurred while finding the page.

Action:
Contact Oracle Support Services.

WCS-19272
Error in processing the pages.

Category:
Other

Cause:
Unexpected error occurred while creating the menu model.

Action:
Contact Oracle Support Services.

WCS-19273
Error in navigation.

Category:
Other

Cause:
Unexpected error occurred while navigating to secondary page.

Action:
Contact Oracle Support Services.

WCS-19274
Error in processing the pages.

Category:
Other

Cause:
Unexpected error occurred while preparing the children.

Action:
Contact Oracle Support Services.

WCS-19275
Error in processing the pages.

Category:
Other

Cause:
Unexpected error occurred while preparing the page for current request.

Action:
Contact Oracle Support Services.

WCS-19276
Error in navigation.

Category:
Other

Cause:
Unexpected error occurred while getting the navigable path to the page.

Action:
Contact Oracle Support Services.

WCS-19277
An error occurred while changing the page visibility. Refresh the page list and retry.

Category:
Other

Cause:
Unexpected error occurred while changing the page's visibility.

Action:
Contact Oracle Support Services.

WCS-19278
Error in renaming the page.

Category:
Other

Cause:
Unexpected error occurred while changing the page name.

Action:
Contact Oracle Support Services.

WCS-19279
Error in creating a copy of the page.

Category:
Other

Cause:
Unexpected error occurred while copying the page.

Action:
Contact Oracle Support Services.

WCS-19280
The role name {0} is reserved, please use some other name.

Category:
Other

Cause:
Unexpected error occurred while creating the role name.

Action:
Try creating a role with some other name.

WCS-19281
Unexpected error occurred while refreshing list of pages.

Category:
Other

Cause:
Unexpected error occurred while refresh.

Action:
Contact Oracle Support Services.

WCS-19282
Unable to save the BusinessRole sequence of pages.

Category:
Other

Cause:
An attempt to customize the BR page sequence failed. Either the back-end store could not be accessed or some other customization operation was performed simultaneously

Action:
Try the operation again. If the problem persists, contact your administrator.

WCS-19283
Error in reordering the pages.

Category:
Other

Cause:
Unexpected error occurred while reordering the pages.

Action:
Contact Oracle Support Services.

WCS-19284
Error in reordering the business role pages.

Category:
Other

Cause:
Unexpected error occurred while reordering the business role pages.

Action:
Contact Oracle Support Services.

WCS-19285
Error in reordering the pages.

Category:
Other

Cause:
Unexpected error occurred while reordering the pages.

Action:
Contact Oracle Support Services.

WCS-19286
Error in moving the page up.

Category:
Other

Cause:
Unexpected error occurred while moving the page up.

Action:
Contact Oracle Support Services.

WCS-19287
Error in moving the page down.

Category:
Other

Cause:
Unexpected error occurred while moving the page down.

Action:
Contact Oracle Support Services.

WCS-19288
Error in processing the pages.

Category:
Other

Cause:
Unexpected error occurred while closing the page.

Action:
Contact Oracle Support Services.

WCS-19289
Unexpected error in closing page(s).

Category:
Other

Cause:
Unexpected error occurred while closing the pages.

Action:
Contact Oracle Support Services.

WCS-19290
Unexpected error in getting list of moderators.

Category:
Other

Cause:
Unexpected error occurred while getting the list of moderators.

Action:
Contact Oracle Support Services.

WCS-19291
Unexpected error occurred in getting the page Uri for the favorites.

Category:
Other

Cause:
Unexpected error occurred while getting the Uri for the favorites.

Action:
Contact Oracle Support Services.

WCS-19292
Unexpected error occurred in creating the new folder.

Category:
Other

Cause:
Unexpected error occurred while creating a new folder.

Action:
Contact Oracle Support Services.

WCS-19293
Unexpected error occurred while getting the list of favorites.

Category:
Other

Cause:
Unexpected error occurred while getting the list of favorites.

Action:
Contact Oracle Support Services.

WCS-19294
Unexpected error occurred while trying to navigate to bookmark.

Category:
Other

Cause:
Unexpected error occurred while trying to navigate to bookmark.

Action:
Contact Oracle Support Services.

WCS-19295
Error occurred while reverting administration changes.

Category:
Other

Cause:
An unexpected error occurred while reverting administration changes.

Action:
Contact system administrator.

WCS-19296
The application failed to access backend data store and cannot process requests

Category:
Other

Cause:
Access to backend data store failed

Action:
Ensure the back-end data store that contains the WebCenter Portal schema and MDS schema is accessible.

WCS-19297
The URL typed by current user is not accessible, so redirecting to the unAuthorized page

Category:
Other

Cause:
The current user does not have privileges to see the current URL

Action:
Please contact system administrator

WCS-19298
Unexpected error occurred, please retry the operation

Category:
Other

Cause:
An internal error occurred

Action:
Retry the operation. Contact Oracle Support Services if the issue persists.

WCS-19299
Unexpected error occurred while preparing the administration pages

Category:
Other

Cause:
An internal error occurred

Action:
Retry the operation. Contact Oracle Support Services if the issue persists.

WCS-19300
Unexpected error trying to restore the Login page

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19301
Unexpected error trying to navigate to the Login page

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19302
Unexpected error trying to open the Login page for edit

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19303
Unexpected error occurred while moving a page to top of the pages list

Category:
Other

Cause:
Unexpected error occurred while moving a page to top of the pages list

Action:
Contact Oracle Support Services.

WCS-19304
Unexpected error occurred while moving a page to bottom of the pages list

Category:
Other

Cause:
Unexpected error occurred while moving a page to bottom of the pages list

Action:
Contact Oracle Support Services.

WCS-19305
Drag and drop is not allowed for ungrouped view

Category:
Other

Cause:
Drag and drop was attempted in ungrouped view

Action:
Drag and drop operation is not allowed for ungrouped view

WCS-19306
Reorder of personal pages is not allowed here

Category:
Other

Cause:
A personal page was selected as either the drag source or the drop target

Action:
Exclude personal pages from drag and drop operations

WCS-19307
Unexpected error occurred while creating mandatory document.

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19308
Failed to grant a role {1} to identity {0} in scope {2}

Category:
Other

Cause:
Failed to find identity {0} in Identity Store while Granting a role {1} in scope {2}

Action:
Create a new Identity {0} in Identity Store and try again

WCS-19309
Unexpected error retrieving services for configuration

Category:
Other

Cause:
An unexpected error occurred

Action:
Contact Oracle Support Services.

WCS-19310
Unexpected error occurred while trying to retrieve list of languages

Category:
Other

Cause:
Unexpected error occurred while trying to retrieve list of languages

Action:
Contact Oracle Support Services.

WCS-19311
Error occurred granting role {0} in {1}. Refresh the members list to see which users were added successfully. Some errors are displayed below. Contact your administrator for a complete list of errors.

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19312
Identities : {0}, failed with the errors {1}

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19313
Setting {0} role for {1} failed. Please contact Administrator

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19314
Portal template {0} is an out-of-the-box template. You cannot export out-of-the-box portal templates.

Category:
Other

Cause:
Portal template is an out-of-the-box template.

Action:
Refer to export documentation for more information or contact your administrator.

WCS-19315
One or more pages of portal {0} are being edited by other users. Wait for some time and try again.

Category:
Other

Cause:
One or more portal pages are being edited by other users. You cannot export when pages are in edit mode.

Action:
Close all the pages from edit mode or contact the administrator.

WCS-19316
One or more pages of portal {0} are being edited by other users. Wait for some time and try again.

Category:
Other

Cause:
One or more portal pages are being edited by other users. You cannot import when pages are in edit mode..

Action:
Close all the pages from edit mode or contact the administrator.

WCS-19317
An unexpected error has occurred while sending notification to the administrator.

Category:
Other

Cause:
An unexpected error occurred

Action:
Contact Oracle Support Services.

WCS-19318
Granting of Role {0} partially succeeded for identity {1}. Granting permissions for {2} failed.

Category:
Other

Cause:
Granting of Role for certain Services failed due to RoleMapping Exception

Action:
Please check the log for actual error stack.

WCS-19319
Revoking of Role {0} partially succeeded for identity {1}. Revoking permissions for {2} failed.

Category:
Other

Cause:
revoking of Role for certain Services failed due to RoleMapping Exception

Action:
Please check the log for actual error stack.

WCS-19320
File {0} already exists. Do you want to overwrite it?

Category:
Other

Cause:
File already exists in the location where the export archive is being saved.

Action:
Provide a new file name or overwrite the file.

WCS-19321
Issues were faced while provisioning the service(s) - {0}. Check the portal services settings page if these services have been provisioned.

Category:
Other

Cause:
While provisioning the services, errors were encountered for certain services.

Action:
Contact administrator.

WCS-19322
You do not have sufficient permission to edit the page.

Category:
Other

Cause:
Your permission to edit the page might have been revoked.

Action:
Contact the administrator.

WCS-19323
The image file {0} you tried to upload was invalid. Provide a valid image file.

Category:
Other

Cause:
Unable to upload the image as the file is null or invalid.

Action:
Upload a valid image file

WCS-19324
An error occurred while cleaning the pages from persistence store for current user.

Category:
Other

Cause:
An unexpected error occurred while cleaning the list of pages.

Action:
Contact system administrator.

WCS-19325
One needs to login to access this url {0}

Category:
Other

Cause:
Public Users don't have access to this url

Action:
Please login first.

WCS-19326
Couldn''t invalidate joc region {0} due to {1}

Category:
Other

Cause:

Action:

WCS-19327
Could not delete joc region {0} due to {1}

Category:
Other

Cause:

Action:

WCS-19328
Could not add object {1} to joc region {0} due to {2}

Category:
Other

Cause:

Action:

WCS-19329
Could not replace object {1} in joc region {0} due to {2}

Category:
Other

Cause:

Action:

WCS-19330
Could not retrieve object {1} from joc region {0} due to {2}

Category:
Other

Cause:

Action:

WCS-19331
Could not invalidate object {1} in joc region {0} due to {2}

Category:
Other

Cause:

Action:

WCS-19332
Unexpected error occurred while processing roles in {0}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19333
Unexpected error occurred while processing users in {0}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19334
Unexpected error occurred while retrieving all users who have been assigned {0} in {1}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19335
Could not validate user due to {0}

Category:
Other

Cause:

Action:

WCS-19336
Unexpected error occurred while retrieving enterprise roles for user {0}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19337
Unexpected error occurred while retrieving application role {0}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19338
Could not retrieve display name for user {0} due to {1}

Category:
Other

Cause:

Action:

WCS-19339
Unable to retrieve user mail ID for {0} due to {1}

Category:
Other

Cause:

Action:

WCS-19340
Unable to retrieve members mailing list for {0} due to {1}

Category:
Other

Cause:

Action:

WCS-19341
Could not verify lifecycle block status due to {0}

Category:
Other

Cause:

Action:

WCS-19342
Unexpected error occurred while retrieving users / groups who have been granted application role {0}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact the administrator.

WCS-19343
Unable to send notification to administrator(s). The reason is : {0}.

Category:
Other

Cause:
The BPEL server is not configured

Action:
Configure workflows.

WCS-19344
User(s) {0} has already been invited to portal.

Category:
Other

Cause:
An unexpected error occurred while inviting users.

Action:
Contact system administrator.

WCS-19345
Errors occurred in inviting user(s) to join the portal {1} as role {0}. Please refresh the members list below to see the latest status about the invited users. Some of the errors are displayed below(Please note that following list may not be listing all the errors. For the complete list of errors, please contact the administrator).

Category:
Other

Cause:
An unexpected error occurred while inviting users.

Action:
Contact system administrator.

WCS-19346
User {0} not invited to portal {1}.

Category:
Other

Cause:
User {0} not invited to portal {1}.

Action:
Contact system administrator.

WCS-19347
The default shell-config document cannot be read for looking up application-specific URL parameters, due to {0}.

Category:
Other

Cause:
The metadata repository might be down or the document may have got corrupted.

Action:
Verify that the metadata repository is up and the document contents are valid.

WCS-19348
Error occurred during permissions related operations. Refresh the roles screen to see the updated information. Contact your administrator for the list of errors.

Category:
Other

Cause:
An unexpected error occurred during permission related operations.

Action:
Contact system administrator.

WCS-19349
Could not find application role matching the search string {0} due to {1}.

Category:
Other

Cause:

Action:

WCS-19350
Removing role mapping related to service {0} failed due to {1}.

Category:
Other

Cause:

Action:

WCS-19351
Could not send notification to administrator as server may be down or Portal workflows are not accessible. Try again after some time.

Category:
Other

Cause:
Failed to connect to SOA server.

Action:
Check if the SOA server is up or if Portal workflows are deployed on SOA server.

WCS-19352
Unable to complete the export process as required resources are not available. Another export or import process might be in progress. Please try export again after sometime.

Category:
Other

Cause:
Export operation failed. Either another export process or portal operation is in progress.

Action:
Wait for some time and try the export operation again. If the problem persists, contact the administrator.

WCS-19353
Import failed. The portal archive contains new portals without security information.

Category:
Other

Cause:
The portal archive you are trying to import contains new portals without security. All new portals must include security information.

Action:
Export the portals again with security and try again. If the problem persists, contact the administrator.

WCS-19354
The page {0} (in {1}) cannot be copied due to {2}.

Category:
Other

Cause:
An error occurred while trying to copy the page.

Action:
Refine the logging level, retry the operation, and check the logs for more information about the error, or contact Oracle Support Services.

WCS-19355
Unable to make updates to the attributes of the page {0} due to {1}.

Category:
Other

Cause:
An error occurred while trying to make updates to the page attributes.

Action:
Refine the logging level, retry the operation, and check the logs for more information about the error, or contact Oracle Support Services.

WCS-19356
Unable to open the requested page.

Category:
Other

Cause:
An unexpected error while opening the page or while creating a copy of it for editing.

Action:
Contact the administrator.

WCS-19357
Could not find the page label due to {0}.

Category:
Other

Cause:

Action:

WCS-19358
Identity(s) {0} has already been added to portal.

Category:
Other

Cause:
An unexpected error occurred while adding users.

Action:
Contact system administrator.

WCS-19359
You cannot invite yourself as a member.

Category:
Other

Cause:
Operation not allowed.

Action:
Contact system administrator.

WCS-19360
Could not retrieve the role {0}. Please contact administrator.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact system administrator.

WCS-19361
Could not find the page visibility due to {0}.

Category:
Other

Cause:

Action:

WCS-19362
You cannot add yourself as a member.

Category:
Other

Cause:
Operation not allowed.

Action:
Contact system administrator.

WCS-19363
SDP Messaging URL cannot be obtained due to {0}

Category:
Other

Cause:

Action:

WCS-19364
Unable to compute context URL for page {0} with title {1}.

Category:
Other

Cause:

Action:

WCS-19365
Unable to change password. Contact administrator.

Category:
Other

Cause:
An unexpected error occurred while setting the password.

Action:
Contact system administrator.

WCS-19366
Export failed. The export process took too long to complete. Use the export WLST command to perform this export operation.

Category:
Other

Cause:
Export timeout occurred. Either the export set is too large or the policy store information to be exported is too large.

Action:
Try exporting fewer portals or use WLST to perform the export operation.

WCS-19367
Import failed. The import process took too long to complete. Use the import WLST command to perform this import operation.

Category:
Other

Cause:
Import timeout occurred. Either the import set is too large or the policy store information to be imported is too large.

Action:
Try importing fewer portals or use WLST to perform the import operation.

WCS-19368
Could not find the secondary tab for the current request. PrimaryTab found : {0}, SubTabs : {1}, LastAccesedPage(From previous session) : {2}, Page service cache : {3}

Category:
Other

Cause:

Action:

WCS-19369
Get Member Info not supported for scope

Category:
Other

Cause:
Currently get Member Info not supported.

Action:
Contact the administrator.

WCS-19370
You can not invite a group for the portal subscription

Category:
Other

Cause:
Inviting group is not supported

Action:
Please contact the administrator.

WCS-19371
Failed to read the notification message from backend datastore

Category:
Other

Cause:
Notification message is null, try setting it

Action:
Please contact the administrator.

WCS-19372
Group name is empty

Category:
Other

Cause:
Given group name is empty

Action:
Please pass the correct group name

WCS-19373
Granting of role {0} failed for identities {1}.

Category:
Other

Cause:
Exception occurred while granting a role {0} to identities {1}

Action:
Please check the log for actual error stack.

WCS-19374
Group {0} grant to {1} failed for users {2}. The following users are already granted a role: {3}

Category:
Other

Cause:
An internal error occurred

Action:
Contact Oracle Support Services.

WCS-19375
Group {0} is not found in Identity Store

Category:
Other

Cause:
Given group name is not found

Action:
Please pass the correct group name

WCS-19376
{0} User(s) including {1} have already been granted role(s) {2}.

Category:
Other

Cause:
User(s) already granted roles.

Action:
User(s) already granted roles.

WCS-19377
Group(s) {0} has already been granted role(s).

Category:
Other

Cause:
Group(s) already granted role(s)

Action:
Group(s) already granted role(s)

WCS-19378
Unable to grant role mapping permissions for role {0} in scope {1}

Category:
Other

Cause:
The role was not granted role mapping permissions. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-19379
Unable to drop role mapping permissions for role {0} in scope {1}

Category:
Other

Cause:
There was an error while dropping role mapping permissions for the role. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-19380
Unexpected error while restoring the Default Profile Gallery Page.

Category:
Other

Cause:
There was an error while removing the profile page customization. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-19381
Unexpected error occurred while setting the language

Category:
Other

Cause:
Unexpected error occurred while trying to save the language choice

Action:
Contact Oracle Support Services.

WCS-19382
Copying of members failed for following identities {0}

Category:
Other

Cause:
Copying of members failed for following identities {0}.

Action:
Try again after some time or Contact Administrator.

WCS-19383
Operation not allowed on child portal {0}

Category:
Other

Cause:
Child portal does not support the operation.

Action:
Perform on correct parent portal or Contact Administrator.

WCS-19384
Unexpected error occurred while getting the list of page templates

Category:
Other

Cause:
Unexpected error occurred while getting the list of Page Templates

Action:
Contact Oracle Support Services.

WCS-19385
Unexpected error occurred while getting the list of Resource Catalogs

Category:
Other

Cause:
Unexpected error occurred while getting the list of Resource Catalogs

Action:
Contact Oracle Support Services.

WCS-19386
Unexpected error occurred while getting the languages

Category:
Other

Cause:
Unexpected error occurred while trying to retrieve the languages

Action:
Contact Oracle Support Services.

WCS-19387
Unexpected error occurred while creating translations for the imported portal.

Category:
Other

Cause:
Unexpected error occurred while creating the translations.

Action:
Contact Administrator

WCS-19388
Unexpected error occurred while collapsing the sidebar

Category:
Other

Cause:
Unexpected error occurred while

Action:
Contact Oracle Support Services.

WCS-19389
Unexpected error occurred while expanding the sidebar

Category:
Other

Cause:
Unexpected error occurred while

Action:
Contact Oracle Support Services.

WCS-19390
Unexpected error occurred while getting the list of recently accessed portals.

Category:
Other

Cause:
Unexpected error occurred while getting the list of recently accessed portals.

Action:
Contact Oracle Support Services.

WCS-19391
Unexpected error downloading vcard

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-19392
Unexpected error looking up user profile

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-19393
Unexpected error launching resource

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-19394
Unexpected error occurred while getting the list of portals current user can access.

Category:
Other

Cause:
Unexpected error occurred while getting the list of portals current user can access.

Action:
Contact Oracle Support Services.

WCS-19395
A page named {0} already exists.

Category:
Other

Cause:
A page with the specified name exists.

Action:
Specify a unique name for the page.

WCS-19396
Unexpected error while restoring the Default Page.

Category:
Other

Cause:
There was an error while removing the page customization. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-19397
Unexpected error while changing the permission model for portal {0}.

Category:
Other

Cause:
Unexpected error while changing the permission model for portal {0}.

Action:
Contact Administrator.

WCS-19398
No users/groups selected

Category:
Other

Cause:
No users/groups were selected to perform the requested operation on.

Action:
Select one or more users/groups and retry the operation.

WCS-19399
Exception occurred while searching groups for a user :{0}

Category:
Other

Cause:
An unexpected error/exception occurred.

Action:
Contact Oracle Support Services.

WCS-19400
Failed to determine public access on page {0} due to {1}

Category:
Other

Cause:
An unexpected error/exception occurred.

Action:
Contact Oracle Support Services.

WCS-19401
"Unexpected error getting read lock on {0}

Category:
Other

Cause:
An unexpected error/exception occurred.

Action:
Contact Oracle Support Services.

WCS-19402
Error determining the template for the current page

Category:
Other

Cause:
Unexpected severe error.

Action:
Contact Administrator.

WCS-19403
Error occurred while fetching the list of navigations.

Category:
Other

Cause:
Unexpected error while fetching list of navigations.

Action:
Contact Administrator.

WCS-19404
Scope list cannot be empty.

Category:
Other

Cause:
Unexpected error while fetching list of portals.

Action:
Contact Administrator.

WCS-19405
Unable to set the security parent of {0} to {1}.

Category:
Other

Cause:
Unexpected error while setting the security parent.

Action:
Contact Administrator.

WCS-19406
Unable to delete base docs from archive.

Category:
Other

Cause:
Unexpected error while deleting base docs from archive.

Action:
Contact Administrator.

WCS-19407
Resources conflict. Base resource on target is not same as the base resource on source. Import cannot proceed.

Category:
Other

Cause:
Resources conflict occurred at the target.

Action:
Contact Administrator.

WCS-19408
Unable to flush changes for deleted base docs from archive.

Category:
Other

Cause:
Unexpected error while deleting base docs from archive.

Action:
Contact Administrator.

WCS-19409
Could not create site registry as folder does not exists.

Category:
Other

Cause:
Unexpected error while creating the site registry.

Action:
Contact Administrator.

WCS-19410
Error occurred while refreshing template cache.

Category:
Other

Cause:
Unexpected error occurred while refreshing template cache.

Action:
Contact Administrator.

WCS-19411
{0}.

Category:
Other

Cause:
Unexpected error while fetching list of navigations.

Action:
Contact Administrator.

WCS-19412
Error occurred while saving the custom attributes in metadata.

Category:
Other

Cause:
Unexpected error occurred while saving the custom attributes in metadata.

Action:
Contact Administrator.

WCS-19413
Error occurred while granting permission to portal {0} for the provisioned service(s).

Category:
Other

Cause:
Unexpected error occurred while granting permission.

Action:
Contact Administrator.

WCS-19414
Error occurred while checking for portal permission.

Category:
Other

Cause:
Error occurred while checking community manage permission.

Action:
Contact Administrator.

WCS-19415
For user {0}, couldn"t retrieve the list of pages last accessed due to {1}

Category:
Other

Cause:

Action:

WCS-19416
Check for valid repository failed.

Category:
Other

Cause:
Either the database is down or the WebCenter Portal repository is not installed.

Action:
Check the exception's details to why this error occurred.

WCS-19417
For user {0}, the last accessed page couldn''t be found due to {1}

Category:
Other

Cause:

Action:

WCS-19418
For user {0}, couldn''t clean the last accessed page due to {1}

Category:
Other

Cause:

Action:

WCS-19419
For user {0}, couldn''t retrieve the last accessed page in {1} due to {2}

Category:
Other

Cause:

Action:

WCS-19420
Unexpected error occurred while checking custom access for the portal {0}.

Category:
Other

Cause:
Likely the authorizer class specified in WebCenter Portal configuration could not be accessed. Review the underlying exception in the logs to determine the exact cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-19421
Denying access for scope {0} as {1} property not specified in WebCenter Portal configuration

Category:
Other

Cause:
The authorizer class is not specified against specified property in WebCenter Portal Configuration

Action:
Define the specified property pointing to the required ResourceAuthorizer implementation in WebCenter Portal configuration

WCS-19422
Grant Role to Role Mapped Service for Portal User role not supported in scope {0}

Category:
Other

Cause:
Grant Role to Role Mapped Service for Portal User role not supported in scope {0}.

Action:
Do not try this operation in this scope

WCS-19423
Grant Role to Role Mapped Service for Public User role not supported in scope {0}

Category:
Other

Cause:
Grant Role to Role Mapped Service for Public User role not supported in scope {0}.

Action:
Do not try this operation in this scope

WCS-19424
Unable to delete site resource registry file from archive.

Category:
Other

Cause:
Unexpected error while deleting site resource registry file from archive.

Action:
Contact Administrator.

WCS-19425
Checking whether portal is published to Portal user is not supported in Home Portal.

Category:
Other

Cause:
An attempt was made to check whether the portal is published to Portal user in Home portal.

Action:
This API must be invoked in the context of portal and not Home portal

WCS-19426
Encountered exception: {0}. For diagnosis, turn on the logging level to FINEST and retry the operation. Details about the current state: {1}

Category:
Other

Cause:
An exception was encountered unexpectedly.

Action:
Turn on the logging level to FINEST and retry the operation.

WCS-19427
Error in setting Show Page of the business role page.

Category:
Other

Cause:
Unexpected error occurred while setting Show Page of the business role page.

Action:
Contact Oracle Support Services.

WCS-19428
Unexpected error occurred while importing the security policy. Unable to import the policy store.

Category:
Other

Cause:
An unexpected error occurred while importing policy store metadata from the import archive.

Action:
Contact Oracle Support Services.

WCS-19429
Unexpected error occurred while checking if the current user can {0} the scope {1}.

Category:
Other

Cause:
Unexpected error occurred while checking if the current user can {0} the scope {1}.

Action:
Try again later or contact administrator

WCS-19430
Unexpected error occurred while checking if the current user can {0} the asset {1} in scope {2}.

Category:
Other

Cause:
Unexpected error occurred while checking if the current user can {0} the asset {1} in scope {2}.

Action:
Try again later or contact administrator

WCS-19431
Unexpected error occurred while fetching roles for user {0} in portal {1}.

Category:
Other

Cause:
Unexpected error occurred while fetching roles for user {0} in portal {1}.

Action:
Try again later or contact administrator

WCS-19432
Fetching the roles of current user is not supported in default scope.

Category:
Other

Cause:
Fetching the roles of current user is not supported in default scope.

Action:
Do not try this operation

WCS-19433
Unexpected error occurred while setting action {0} to role {1}.

Category:
Other

Cause:
Unexpected error occurred while setting action {0} to role {1}.

Action:
Contact Administrator

WCS-19434
Fatal error occurred while getting members count.

Category:
Other

Cause:
An unexpected error occurred while getting the members count.

Action:
Please contact the administrator.

WCS-19435
Couldn''t get the first accessible page for the Home portal due to {1}.

Category:
Other

Cause:
Error in getting the first accessible page for the Home portal.

Action:
Contact the application administrator.

WCS-19436
The community query permission is not found

Category:
Other

Cause:
The community query permission is not found.

Action:
Contact the application administrator.

WCS-19437
The community manage membership permission is not found

Category:
Other

Cause:
The community manage membership permission is not found.

Action:
Contact the application administrator.

WCS-19438
The community view membership permission is not found

Category:
Other

Cause:
The community view membership permission is not found.

Action:
Contact the application administrator.

WCS-19439
The community edit membership permission is not found

Category:
Other

Cause:
The community edit membership permission is not found.

Action:
Contact the application administrator.

WCS-19440
One or more pages of portal {0} is being edited by other users. The export archive may not contain the page changes.

Category:
Other

Cause:
One or more portal pages is being edited by other users. The export archive may not contain the page changes.

Action:
Close all pages open in edit mode and try again.

WCS-19441
One or more pages of portal {0} is being edited by other users. The import may not complete properly.

Category:
Other

Cause:
One or more portal page is in edit mode. The import may not complete properly.

Action:
Close all pages open in edit mode and try again.

WCS-19442
Invalid input - unmatched quotes

Category:
Other

Cause:
A string was provided with unmatched quotes.

Action:
Ensure all quotes are opened and closed.

WCS-19450
Unable to fetch custom property {0} at the application level

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-19451
Unable to fetch custom property {0} from scope {1}

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-19452
Could not initialize Default Portal Setting

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-19453
Could not update the default portal identity settings

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-19454
Could not update the default portal public setting

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-19455
Could not update the default portal default setting

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-19456
Could not set the redirect on login setting for default portal

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-19457
Could not update default portal settings to handle rename of portal from {0} to {1}

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details. Change the portal manually in Administration screens

WCS-19458
Could not update default portal settings to handle delete of portal {0}

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details. Change the portal manually in Administration screens

WCS-19459
The default portal configuration is being modified by another user. Try operation after some time.

Category:
Other

Cause:
>Another admin user is updating the default portal configuration

Action:
Try the operation after some time

WCS-19460
Could not fetch the default portal configuration from webcenter-config

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Go the Default Portal Configuration screen and change the default setting to desired values

WCS-19461
Unexpected error while fetching the default portal due to {0}

Category:
Other

Cause:
Unexpected error while fetching the default portal

Action:
Unexpected error while fetching the default portal

WCS-19462
User {0} does not have the privileges required for this operation on Portals/Portal Templates. Verify that the user has "Create Portal" permission while performing import or deployment operation, "Create and Manage Portal" permission while performing redeployment operation and "Manage Portal" permission while performing export or propagation operation.

Category:
Other

Cause:
Check if the user has required permission on Portals for performing lifecycle operations.

Action:
Try performing the operation as an administrator.

WCS-19463
Error occurred while importing the security policy as the UCM server is down.

Category:
Other

Cause:
Error occurred while importing the security policy as the UCM server is down.

Action:
Start the UCM server and retry this operation

WCS-19464
User {0} not authorized to view Application.

Category:
Other

Cause:
User not authorized to view Application

Action:
Contact Administrator to grant more permissions.

WCS-19465
User {0} not authorized to configure Application.

Category:
Other

Cause:
User not authorized to configure Application

Action:
Contact Administrator to grant more permissions.

WCS-19466
Error occurred in creating translated scope resource bundle {0} due to {1}.

Category:
Other

Cause:
Unexpected error while creating scope resource bundle for newly created Portal/Template.

Action:
Take action based on the underlying exception details.

WCS-19467
Error occurred while parsing document name due to {0}.

Category:
Other

Cause:
Unexpected error while parsing scope resource bundle file name.

Action:
Take action based on the underlying exception details.

WCS-19468
Unexpected error occurred while adding Business Role Page for Impersonation due to {0}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-19469
Error occurred while adding Impersonation page:{0} to pages:{1} due to {2}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-19470
Error occurred while granting navigation permissions for role {0} for the scope {1} due to {2}

Category:
Other

Cause:
An unexpected error occurred while granting the user permission

Action:
Contact the WebCenter Portal administrator

WCS-19471
Error occurred while deleting the list of tabs to persistence store

Category:
Other

Cause:
An unexpected error occurred while deleting the list of pages.

Action:
Contact system administrator.

WCS-19472
Unexpected error occurred while fetching current device group due to {0}

Category:
Other

Cause:
Unexpected error occurred while fetching current device group due to {0}

Action:
Contact Administrator for more details

WCS-19473
Get GUID call for LibOVDUser {0} returned null, which caused NullPointerException.

Category:
Other

Cause:
Misconfiguration found in jps-config.xml.

Action:
Please contact the WebCenter Portal administrator.

WCS-19474
There are no Portal Server URL connections set.

Category:
Other

Cause:
There are no Portal Server URL connections set for deploying the portals.

Action:
Please create a Portal Server URL Connection.

WCS-19475
Failed to update application ready status

Category:
Other

Cause:
Status update to indicate application readiness with ReadyApp failed. There may be issues with registering or configuring the application.

Action:
Examine WebLogic Server debug logs for further details.

WCS-19476
Failed to update application not ready status

Category:
Other

Cause:
Status update to indicate application non-readiness with ReadyApp failed. There may be issues with registering or configuring the application.

Action:
Examine WebLogic Server debug logs for further details.

WCS-19477
Creation of seeded role is not supported for scope {0}

Category:
Other

Cause:
Currently the creation of seeded role is not supported.

Action:
Contact the administrator.

WCS-19478
Unable to grant permissions to {0} role in the policy store

Category:
Other

Cause:
An attempt to grant permissions failed due to unexpected errors.

Action:
Determine the cause and, if necessary, try again.

WCS-19479
Password does not adhere to password policy. {0}

Category:
Other

Cause:
Password does not adhere to password policy.

Action:
Password must adhere to password policy.

WCS-19480
The Web Address contains invalid characters. Make sure the Web Address begins with "/portal", "/webcenter", "http://", or "https://"

Category:
Other

Cause:
The Web Address contains invalid character.

Action:
Input valid characters.

WCS-19481
The Location contains invalid characters and make sure it begins with "/portal", "/webcenter", "http://", or "https://"

Category:
Other

Cause:
The Location contains invalid character.

Action:
Input valid characters.

WCS-26001
Search Configuration Error: {0}

Category:
Other

Cause:
A configuration error has been encountered.

Action:
Refer to the error details and the documentation for how to debug this.

WCS-26021
Invalid Query {0}.

Category:
Other

Cause:
An invalid query was sent.

Action:
Query validity is dependent on the service running it. Refer to the query in the log and the documentation for the service involved to debug this.

WCS-26022
Contradiction caused when clause "{0}" is added to "{1}"

Category:
Other

Cause:
An unexpected programming error occurred. This is not something that can be fixed.

Action:
Contact Oracle Support Services.

WCS-26023
The addition of criteria to {0} existing date criterion is not supported

Category:
Other

Cause:
An unexpected programming error occurred. This is not something that can be fixed.

Action:
Contact Oracle Support Services.

WCS-26041
General Search Execution Error

Category:
Other

Cause:
A general execution error has been encountered.

Action:
Query execution error is dependent on the service running it. Refer to the Query in the log and the documentation for the service involved to debug this.

WCS-26042
The execution of the query does not complete within the execution time limit

Category:
Other

Cause:
The search query does not complete within the time limit.

Action:
Re-try the search query again later.

WCS-26061
General Search Response Error

Category:
Other

Cause:
A general response error has been encountered.

Action:
Query execution response error is dependent on the service running it. Refer to the Query in the log and the documentation for the service involved to debug this.

WCS-26062
Query results are immutable; removing elements from it is unsupported.

Category:
Other

Cause:
A caller tried to remove an element from the result set.

Action:
Inform the caller that this is not a supported function.

WCS-26063
SQL ResultSet consumption failed with the message "{0}".

Category:
Other

Cause:
A SQL ResultSet cannot be consumed.

Action:
Refer to the underlying exception to debug this.

WCS-26064
Cannot call "remove" method before calling "next" method.

Category:
Other

Cause:
Caller tried to call "remove" method of QueryResult class before calling "next" method.

Action:
Inform the caller that this is an illegal operation.

WCS-26065
Cannot convert "{0}" value to "{1}".

Category:
Other

Cause:
The target object had no "valueOf" method to convert the source.

Action:
No action is needed; appropriate contingencies have been applied.

WCS-26066
Parameter type {0} cannot be converted into a primitive type.

Category:
Other

Cause:
The conversion failed because the bean property was not of primitive type.

Action:
No action is needed; appropriate contingencies have been applied.

WCS-26081
General Search Authentication Error

Category:
Other

Cause:
A general authentication error has been encountered.

Action:
Query execution authentication error is dependent on the service running it. Refer to the Query in the log and the documentation for the service involved to debug this.

WCS-26091
Search API Implementation error in {0} class

Category:
Other

Cause:
An implementation error has been encountered.

Action:
Report to the provider of the Search API Implementation.

WCS-26101
An error occurred while parsing an XML document at {0}.

Category:
Other

Cause:
The XML document in question may not be well-formed or valid with respect to the referred XML schema.

Action:
Examine the XML document again and check the XML schema to make sure there are not any mistakes or typos.

WCS-26102
An error occurred while parsing the search configuration in adf-config.xml at {0}.

Category:
Other

Cause:
The XML fragment within adf-config.xml may not be well-formed or valid with respect to what is expected for search configuration.

Action:
Examine the adf-config.xml document again and check the documented XML schema to make sure there are not any mistakes or typos.

WCS-26103
An unexpected XML error occurred.

Category:
Other

Cause:
Something with the underlying XML system or implementation of JAXP failed unexpectedly.

Action:
Check the nested exception for more information.

WCS-26121
A general MDS error has occurred.

Category:
Other

Cause:
An MDS-related error has occurred. Something with the MDS setup is misconfigured.

Action:
Check the nested exception for more information.

WCS-26122
An MDS error has occurred because a Metadata Object by the name of {0} cannot be found.

Category:
Other

Cause:
An MDS Metadata Object was not found.

Action:
Check the details of the Metadata Object and check the MDS repository to confirm that it is there.

WCS-26123
Encountered "{0}" with message "{1}" when committing MDS changes.

Category:
Other

Cause:
Something within the current MDS Session cannot be committed.

Action:
Contact Oracle Support Services.

WCS-26124
Saved Search Deletion aborted because the Metadata Object (MO) Reference for ID "{0}" is not found.

Category:
Other

Cause:
The system is in an inconsistent state allowing deletion of non-existent MDS documents

Action:
There is nothing to be done about this. No deletion is performed.

WCS-26125
Encountered "{0}" with message "{1}" while formulating the final MDS Condition.

Category:
Other

Cause:
Some MDS conditions that are being joined caused a failure to come up with the final condition.

Action:
Contact Oracle Support Services.

WCS-26126
MDS query result is null

Category:
Other

Cause:
MDS query result set is null. The MDS repository might be unavailable.

Action:
Perform the operation again after MDS repository becomes available again.

WCS-26141
A configuration error has occurred for the Search service model. The offending configuration is {0}.

Category:
Other

Cause:
The Search service keeps its configuration in adf-config.xml, connections.xml, and MDS.

Action:
Check in the appropriate configuration files to see if there are any obvious erroneous data.

WCS-26142
A security error has occurred for the Search service model. The offense is {0}.

Category:
Other

Cause:
The Search service model security maintained by the service caused a failure.

Action:
Check the security settings for each underlying service to identify any anomalies.

WCS-26143
Failed to commit changes to Search preferences, encountering {0}.

Category:
Other

Cause:
Some underlying MDS issues with the Preferences implementation is causing the failure.

Action:
Contact Oracle Support Services.

WCS-26144
An error occurred while parsing the default full crawl interval "{0}".

Category:
Other

Cause:
An internal error occurred while trying to instantiate a DatatypeFactory for parsing Duration values.

Action:
Contact Oracle Support Services.

WCS-26145
An invalid full crawl interval "{0}" was specified in adf-config.xml.

Category:
Other

Cause:
The fullCrawlInterval attribute of the crawl-properties element in adf-config.xml may not be well-formed or valid.

Action:
Make sure that the fullCrawlInterval attribute value is in the duration format as defined in the W3C XML Schema 1.0.

WCS-26146
An invalid full crawl interval "{0}" was specified for service {1}.

Category:
Other

Cause:
The fullCrawlInterval attribute of a service-crawl-properties element in adf-config.xml may not be well-formed or valid.

Action:
Make sure that the fullCrawlInterval attribute value is in the duration format as defined in the W3C XML Schema 1.0.

WCS-26147
An error occurred while parsing the crawl-properties element in adf-config.xml.

Category:
Other

Cause:
An internal error occurred while trying to parse the crawl-properties element in adf-config.xml.

Action:
Contact Oracle Support Services.

WCS-26161
Encountered a message from MDS indicating unsupported operation while deleting a Saved Search with ID "{0}", MO Reference name "{1}", and MO Absolute Name "{2}".

Category:
Other

Cause:
The deletion of a Saved Search triggered some MDS operation that is not supported on said Saved Search document.

Action:
Contact Oracle Support Services

WCS-26162
A saved search with name "{0}" already exists, use a different name.

Category:
Other

Cause:
The name you provided is used already.

Action:
Use a different name when saving your searches.

WCS-26163
Duplicated identifier found while adding a saved search with a identifier "{0}" with Metadata Object name "{1}"; replacing with "{2}".

Category:
Other

Cause:
The system is in an inconsistent state where an old ID is used on a new Saved Search.

Action:
This is a cautionary message only. Appropriate actions will be taken to fix the uniqueness issue.

WCS-26164
Encountered an MDS exception "{1}" with message "{2}" while querying for saved searches with condition "{0}".

Category:
Other

Cause:
An underlying MDS exception occurred during the query execution.

Action:
Contact Oracle Support Services.

WCS-26165
Failed to retrieve a Saved Search in MDS with Metadata Object reference name "{0}", and absolute name "{1}".

Category:
Other

Cause:
This can be due to an MDS misconfiguration issue.

Action:
Contact Oracle Support Services.

WCS-26166
Failed to retrieve most recent Saved Searches in MDS with Metadata Object reference name "{0}", and absolute name "{1}".

Category:
Other

Cause:
This can be due to an MDS misconfiguration issue.

Action:
Contact Oracle Support Services.

WCS-26167
Encountered an MDS exception "{2}" with message "{3}" while saving a saved search with Metadata Object name "{0}", and absolute name "{1}".

Category:
Other

Cause:
This can be due to an MDS misconfiguration issue.

Action:
Refer to MDS documentation to resolve a lookup failure with the given details.

WCS-26168
Encountered an MDS exception "{2}" with message "{3}" while deleting a saved search with Metadata Object name "{0}", and absolute name "{1}".

Category:
Other

Cause:
An underlying MDS exception caused this.

Action:
Contact Oracle Support Services.

WCS-26169
Encountered an MDS reference exception "{1}" with message "{2}" while retrieving Saved Search Metadata Object reference in MDS with Metadata Object absolute name "{0}".

Category:
Other

Cause:
An underlying MDS exception caused this.

Action:
Contact Oracle Support Services.

WCS-26170
Saved Search Update aborted because the Metadata Object (MO) Reference for ID "{0}" is not found.

Category:
Other

Cause:
This can be due to an MDS misconfiguration issue.

Action:
Refer to MDS documentation to resolve a lookup failure with the given details.

WCS-26171
Encountered an MDS exception "{1}" with message "{2}" while creating a document with Metadata Object absolute name "{0}".

Category:
Other

Cause:
An underlying MDS exception caused this.

Action:
Contact Oracle Support Services.

WCS-26181
Failed to retrieve UI Metadata in MDS with Metadata Object reference name "{0}", and absolute name "{1}".

Category:
Other

Cause:
This can be due to an MDS misconfiguration issue.

Action:
Refer to MDS documentation to resolve a lookup failure with the given details.

WCS-26182
Encountered an MDS exception "{2}" with message "{3}" while adding a UI Metadata with identifier "{0}" and Metadata Object name "{1}".

Category:
Other

Cause:
An underlying MDS exception caused this.

Action:
Contact Oracle Support Services.

WCS-26183
Encountered an MDS exception "{1}" with message "{2}" while querying for UI Metadata with condition "{0}".

Category:
Other

Cause:
An underlying MDS exception caused this.

Action:
Contact Oracle Support Services.

WCS-26184
Encountered an MDS reference exception "{1}" with message "{2}" while looking up UI Metadata Object reference in MDS with Metadata Object absolute name "{0}".

Category:
Other

Cause:
An underlying MDS exception caused this.

Action:
Contact Oracle Support Services.

WCS-26185
Encountered an MDS exception "{0}" with message "{1}" while creating default service list in MDS.

Category:
Other

Cause:
An underlying MDS exception occurred during the creation of the service list in the Search UI Metadata.

Action:
Contact Oracle Support Services.

WCS-26186
Encountered an MDS exception "{1}" with message "{2}" while updating UI Metadata Object in MDS with Metadata Object absolute name "{0}".

Category:
Other

Cause:
An underlying MDS exception occurred during the update of the Search UI Metadata.

Action:
The update by this user will be lost. Refresh the page and continue.

WCS-26201
Encountered "{2}" with message "{3}" when loading QueryManager Class "{0}" for service "{1}" in Extension Handler.

Category:
Other

Cause:
Any one of the possible exceptions resulting from loading a class using reflection occurred.

Action:
Contact Oracle Support Services.

WCS-26202
Search Extension Registry loading failed, encountering "{0}" with message "{1}".

Category:
Other

Cause:
There may be misconfiguration in the adf-config.xml file.

Action:
Check your adf-config.xml to see if the Search extension registry is declared. Make sure that the version numbers match those specified in the documentation.

WCS-26203
Cannot access children, encountering "{0}" with message "{1}".

Category:
Other

Cause:
Encountered a Search exception when trying to extract children executors from a Query Federator

Action:
Contact Oracle Support Services.

WCS-26204
Failed in creating a Row QueryHandler for "{0}", encountering "{1}" with message "{2}".

Category:
Other

Cause:
A run time or Search exception was encountered. This can be due to the creation process timing out or any service-specific creation failure.

Action:
Contact Oracle Support Services.

WCS-26205
{0} occurred during the preparation of Query Handler with identifier "{1}".

Category:
Other

Cause:
The Query Handlers are prepared in parallel; the preparation failed because of underlying concurrency mechanism.

Action:
Contact Oracle Support Services.

WCS-26206
Creation of Row QueryHandler did not complete within the time limit for executor {0}.

Category:
Other

Cause:
The time allowed to create a Row QueryHandler is not sufficient.

Action:
If this problem is persistent, increase the value of prepareExecutionTimeoutMs parameter in adf-search-config section of adf-config.xml file.

WCS-26207
Oracle Secure Enterprise Search (SES) is not configured. Search query cannot be executed.

Category:
Other

Cause:
Oracle Secure Enterprise Search (SES) is not configured.

Action:
Oracle Secure Enterprise Search (SES) must be configured before search query can be executed.

WCS-26221
Search execution was interrupted because of "{0}" with message "{1}".

Category:
Other

Cause:
The service search execution was interrupted because of a timeout or a failure.

Action:
Examine the log to determine the root cause and take appropriate debugging steps.

WCS-26222
Search execution failure for service "{0}", encountering "{1}" with message "{2}".

Category:
Other

Cause:
An exception occurred while executing search.

Action:
Examine the log to determine the root cause and take appropriate debugging steps.

WCS-26223
Search executors not initialized due to null Query.

Category:
Other

Cause:
Query is not set so no Query Executors have been initialized.

Action:
No action is necessary; this is just a diagnostic message.

WCS-26224
Query Handler creation of {0} was interrupted.

Category:
Other

Cause:
The Query Handler named took too long to be created and was timed out.

Action:
Increase your prepareTimeoutMs value in the search-config section of the adf-config.xml file

WCS-26225
{0} occurred during Search result transfer of service with identifier "{1}" with message "{2}"

Category:
Other

Cause:
An unexpected exception occurred when transferring search results after execution.

Action:
Contact Oracle Support Services.

WCS-26226
Failed to extract Refiners from executor {0}.

Category:
Other

Cause:
Failure occurred when extracting refiners from the execution results of an executor.

Action:
Inspect the failure message and fix accordingly.

WCS-26227
Column not found for {0}

Category:
Other

Cause:
When formulating an query with a condition based on an attribute, the attribute is not found.

Action:
Inspect your input and make sure that the values for the attributes are one of "name", "title", "description", "creator", "created", "modifier", "modified", and "tags".

WCS-26228
Parsing of date operand "{0}" failed

Category:
Other

Cause:
When formulating an query with a condition based on a date attribute, the date value specified fails to be parsed.

Action:
Inspect your date attribute and make sure that it follows the format: "yyyy-MM-dd"

WCS-26229
Search query execution timed out for service "{0}".

Category:
Other

Cause:
The search query does not complete within the time limit.

Action:
Re-try the search query again later.

WCS-26281
getSessionVersion failed with Exception {0}

Category:
Other

Cause:
Operation to get Sessions Version from SES failed.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26282
getAllFacets failed with Exception {0}

Category:
Other

Cause:
Operation to fetch allfacets from SES failed.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26283
getAllAttributes failed with Exception {0}

Category:
Other

Cause:
Operation to fetch allattributes from SES failed.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26284
getAllAttributes failed with Exception {0}

Category:
Other

Cause:
Operation to fetch all attributes from SES failed.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26322
Skipping consumption of a Date ComplexPredicate with 1 child because its type {0} is not AttributePredicate<Calendar> as expected.

Category:
Other

Cause:
A Date ComplexPredicate was passed down from the query that contains the wrong type for its single child.

Action:
Contact Oracle Support Services.

WCS-26323
Skipping consumption of a Date ComplexPredicate with 2 children because their types {0} and {1} are not AttributePredicate<Calendar> as expected.

Category:
Other

Cause:
A Date ComplexPredicate was passed down from the query that contains the wrong type for both its children.

Action:
Contact Oracle Support Services.

WCS-26324
Skipping consumption of a Date ComplexPredicate with {0} children because we only support at most two.

Category:
Other

Cause:
Too many children are passed down the Date ComplexPredicate when we can only handle two.

Action:
Contact Oracle Support Services.

WCS-26325
Execution of the search query to show all rows did not complete within the time limit for executor {0}.

Category:
Other

Cause:
The time allowed to execute the search query to show all rows is not sufficient.

Action:
Increase the value of showAllExecutionTimeoutMs parameter in adf-search-config section of adf-config.xml file.

WCS-26326
Execution of the search query did not complete within the time limit for executor {0}.

Category:
Other

Cause:
The time allowed to execute the search query is not sufficient.

Action:
If this problem is persistent, increase the value of executionTimeoutMs parameter in adf-search-config section of adf-config.xml file.

WCS-26327
Query execution failed for {0}.

Category:
Other

Cause:
Query execution failed.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26328
Search failure: time out error

Category:
Other

Cause:
Search execution timed out.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26329
Search failure: problem preparing search executor

Category:
Other

Cause:
Unable to create a search executor.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26330
Search failure: problem with execution

Category:
Other

Cause:
Search execution problem.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26331
Search failure: problem with adding refiner

Category:
Other

Cause:
Unable to add refiner.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26332
Search failure: problem with removing refiner

Category:
Other

Cause:
Unable to remove refiner.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26333
Search failure: problem with updating refiner

Category:
Other

Cause:
Unable to update the refiner.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26341
Search UI Metadata Lookup Failed: {0}

Category:
Other

Cause:
The UI Metadata document necessary for rendering Search views could not be found.

Action:
Refer to the error messages presented in the dialog box and act accordingly.

WCS-26342
Search UI Metadata Update Failed: {0}

Category:
Other

Cause:
The UI Metadata document necessary for rendering Search views could not be updated (customized).

Action:
Refer to the error messages presented in the dialog box and act accordingly.

WCS-26343
Search Options Update Failed

Category:
Other

Cause:
An MDS error caused the update of search options to fail.

Action:
Contact Oracle Support Services.

WCS-26361
Failed to update the last used date / time of saved search with ID "{0}".

Category:
Other

Cause:
An MDS error caused the update of the Saved Search document to fail when updating the last accessed date.

Action:
Contact Oracle Support Services.

WCS-26362
Saved Search Update Failed

Category:
Other

Cause:
An error occurred when trying to update a Saved Search.

Action:
Refer to the error messages presented in the dialog box and act accordingly.

WCS-26363
Saved Search Creation Failed

Category:
Other

Cause:
An error occurred when trying to create a Saved Search.

Action:
Refer to the error messages presented in the dialog box and act accordingly.

WCS-26364
Saved Search Deletion Failed

Category:
Other

Cause:
An error occurred when trying to delete a Saved Search.

Action:
Refer to the error messages presented in the dialog box and act accordingly.

WCS-26365
Failed to delete saved search with ID "{0}".

Category:
Other

Cause:
An MDS error caused the deletion of the Saved Search document to fail.

Action:
Contact Oracle Support Services.

WCS-26366
Failed to update the sharing setting of saved search with ID "{0}".

Category:
Other

Cause:
An MDS error caused the update of the Saved Search document to fail when updating the sharing setting.

Action:
Contact Oracle Support Services.

WCS-26367
Saved search with ID "{0}" could not be found.

Category:
Other

Cause:
Saved search was deleted by another user.

Action:
Refresh page to get updated list of saved searches.

WCS-26381
Resource ID is not available to show the resource.

Category:
Other

Cause:
A link to render a resource did not carry the unique identifier for that resource and therefore could not perform the rendering.

Action:
Contact Oracle Support Services.

WCS-26391
Encountered an exception "{2}" with message "{3}" while populating Data Flavor "{0}" of "{1}" class.

Category:
Other

Cause:
Failed to populate the given Data Flavor in the Resource Catalog Adapter.

Action:
Examine the log for the root cause and take appropriate debugging steps.

WCS-26392
Failed to initialize Search service context DirContext Schema with message "{0}"

Category:
Other

Cause:
A naming exception was encountered when binding attributes while initializing the Resource Catalog schema for the Search service.

Action:
Contact Oracle Support Services.

WCS-26393
Failed to get attributes of resource "{0}"

Category:
Other

Cause:
Failed to get attributes of a given resource.

Action:
Examine the log for the root cause and take appropriate debugging steps.

WCS-26396
Search Box Size not a number - "{0}". Using Default size instead.

Category:
Other

Cause:
taskflow parameter passed to this component not an integer.

Action:
Examine the taskflow parameter and replace value with a number.

WCS-26397
Search Taskflow ID does not correspond to a valid taskflow. Using Default taskflow instead.

Category:
Other

Cause:
taskflow parameter passed to this component not a valid taskflow id.

Action:
Examine the taskflow parameter and replace with appropriate value.

WCS-26398
Search Scope ID parameter value is not a Scope object - "{0}".

Category:
Other

Cause:
taskflow parameter EL or value is not a Scope object

Action:
Examine the taskflow parameter and replace value with a valid Scope object.

WCS-26399
Service with service ID: "{0}" is not registered and cannot be included in Categories list.

Category:
Other

Cause:
Service Id is not a registered service.

Action:
Have an administrator remove service from Services to be included list.

WCS-26400
Locale or Service Registry not found.

Category:
Other

Cause:
Taskflow is not in an appropriate application or adf context was lost.

Action:
Refresh page or place taskflow in appropriate template.

WCS-26401
Encountered "{0}" during proxy login with application entity "{1}" to Oracle SES at [{2}], as search user "{3}".

Category:
Other

Cause:
The proxy login operation encountered error. Some underlying exception is causing the error.

Action:
Refer to the root exception and identify the proper debugging steps.

WCS-26402
Received status "{0}" during proxy login with application entity "{1}" to Oracle SES at [{2}], as search user "{3}". Defaulting to public.

Category:
Other

Cause:
The application entity may not have been provisioned in the identity management system used by SES, or its password may have been expired.

Action:
Log on to the Oracle SES administration tool and make sure that the application entity has been provisioned. Then make sure that the account is enabled on the identity management system and has not expired.

WCS-26403
Federation Trusted Entity parameters not configured. Search as public user on Oracle SES.

Category:
Other

Cause:
Federation Trusted Entity parameters not configured.

Action:
Configure Federation Trusted Entity parameters.

WCS-26421
Failed to initialize data group ID from {0} in {1}, encountering {2}

Category:
Other

Cause:
Either the group ID in question does not exist or SES is down.

Action:
Make sure that SES is up and check the group IDs present on SES.

WCS-26422
Failed to discover attributes from {0} in {1}, encountering {2}

Category:
Other

Cause:
Some underlying exception is causing the discovery of attributes from SES to fail.

Action:
Refer to the root exception and identify the proper debugging steps.

WCS-26423
No attributes discovered from {0} in {1}

Category:
Other

Cause:
The SES instance in question does not offer any attributes to query on.

Action:
Confirm that Oracle SES is up.

WCS-26424
Failed to discover info source nodes from {0} in {1}, encountering {2}

Category:
Other

Cause:
Some underlying exception is causing the discovery of info source nodes of SES to fail.

Action:
Refer to the root exception and identify the proper debugging steps.

WCS-26441
Retrieving the SES Reference failed with Connection Architecture

Category:
Other

Cause:
Something occurred when getReference of the SesReferenceable is called.

Action:
Refer to the root exception and identify the proper debugging steps.

WCS-26442
Looking up the SES Connection failed with Connection Architecture

Category:
Other

Cause:
Encountered a JCA ResourceException when calling getConnection on the connection factory for Searchlets.

Action:
Refer to the root exception and identify the proper debugging steps.

WCS-26443
Connection entry "{0}" not found

Category:
Other

Cause:
The specified connection entry is not in connections.xml

Action:
Add the specified connection entry to connections.xml

WCS-26444
Invalid value for addrType attribute in "{1}" entry. Expected value is "{0}"

Category:
Other

Cause:
Incorrect value for addrType attribute found in connections.xml

Action:
Update connections.xml with the correct value for addrType attribute

WCS-26451
Failed to create an instance of class "{0}"

Category:
Other

Cause:
Failed creating an instance of the XML object representing an SES admin object.

Action:
A RuntimeException would have been thrown to propagate the underlying Exception causing this. Please inspect the log to see what else can be done to fix the issue.

WCS-26452
This command is not supported for the version of SES running on the target SES instance.

Category:
Other

Cause:
The version of SES running on the target SES instance does not support this command.

Action:
This command requires SES 11.2.2.2.0 or later.

WCS-26461
Failed to marshal SES Filter for Advanced Search due to JAXB issues - {0}

Category:
Other

Cause:
A JAXB problem has caused the marshalling of an SES filter before sending it to SES for execution.

Action:
Examine the log to look at the XML structure to verify validity.

WCS-26462
SES Search Execution failed, encountering "{0}" with message "{1}".

Category:
Other

Cause:
The cause is embedded in the Exception and can be SES-specific.

Action:
Examine the log files to extract the root cause to identify the proper debugging steps.

WCS-26463
Can not convert SES Result Element value from {0} to {1}

Category:
Other

Cause:
Conversion from SES Result Element value failed.

Action:
No action is needed. The conversion will default to using String

WCS-26464
Cannot find attribute mapping for column {0}

Category:
Other

Cause:
You have specified a column ID that cannot be found in the list of SES attributes.

Action:
Examine your SES installation and make sure the attribute has a valid column ID.

WCS-26465
Failed to create JAXBContext using package {0}

Category:
Other

Cause:
A JAXBContext instance could not be created for the SES cluster deserializer.

Action:
Make sure that the required files can be found in the specified package and that the required classes can be loaded from the classpath.

WCS-26466
Failed to unmarshal byte stream into Cluster

Category:
Other

Cause:
Unmarshalling failed because a JAXBContext instance could not be obtained.

Action:
Make sure that the required files can be found in the specified package and that the required classes can be loaded from the classpath.

WCS-26467
SES search query execution timed out - "{0}" with message "{1}".

Category:
Other

Cause:
The search query does not complete within the time limit.

Action:
Re-try the search query again later.

WCS-26468
Unable to determine whether primary search configuration is elasticsearch.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26481
SearchCrawlExtension class is not found for service {0}

Category:
Other

Cause:
Portal crawler failed to introspect a Crawlable SPI implementation for the involved service, specified by a URL parameter indicating a crawler's intent to crawl said service. This theoretically should never happen because the URL that crawlers would use are all generated by the Search framework code when crawlers access the root feed that we provide. But if a crawler explicitly starts with a particular service, bypassing our root feed, this warning may result.

Action:
Please check the potential crawling SES instances to make sure that there isn't a source that directly targets a service which has no Crawlable implementation.

WCS-26491
The processing and preparing of the control feed for service {0} failed

Category:
Other

Cause:
The processing and preparing of the control feed for service {0} failed. This could mean that there is a fundamental error in the writing the feed content to the output stream which is to be returned to the caller of the URL.

Action:
Most likely there is a network issue which may well be temporary. Restart the crawl again and see if the problem persists.

WCS-26492
The processing and preparing of the data feed for service {0} failed

Category:
Other

Cause:
The processing and preparing of the data feed for service {0} failed. This could mean that there is a fundamental error in the writing the feed content to the output stream which is to be returned to the caller of the URL.

Action:
Most likely there is a network issue which may well be temporary. Restart the crawl again and see if the problem persists.

WCS-26493
No new entries to crawl for service {0}

Category:
Other

Cause:
There are no items to crawl for the service

Action:
This is expected if there are no items available for crawl. If on the contrary, there are artifacts pertaining to this service, then try scheduling crawl again.

WCS-26501
Creation of the Tags service failed.

Category:
Other

Cause:
The Tags service is loaded by reflection. Something may have happened to cause that to fail.

Action:
Check whether the class name logged is accessible through the class path of the WebCenter Web application.

WCS-26502
Query Federator for the Tags service not created because a Tags Service cannot be created.

Category:
Other

Cause:
The creation of the Tags service was unsuccessful causing the subsequent creation of a Row Query Federator for Tagging to fail.

Action:
Check for /META-INF/tagging-class-config.properties and verify that a correct accessible class is specified.

WCS-26503
findSystemResources failed because of invalid arguments passed in to the method: keywords ({0}).

Category:
Other

Cause:
One of the input arguments to findSystemResources was invalid.

Action:
Make sure that arguments passed in to findSystemResources are all valid.

WCS-26504
findSystemTags failed because of invalid arguments passed in to the method: keywords ({0}).

Category:
Other

Cause:
One of the input arguments to findSystemResources was invalid.

Action:
Make sure that arguments passed in to findSystemTags are all valid.

WCS-26505
lookupTag failed because of invalid arguments passed in to the method: tagName ({0}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26506
findFilteredPersonalTags failed because of invalid arguments passed in to the method: userId ({0}), filter ({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26507
findTopFilteredSystemTags failed because of invalid arguments passed in to the method:userId({0}), filter ({1}), count({2}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26508
findTopFilteredPersonalTags failed because of invalid arguments passed in to the method: userId ({0}), filter ({1}), count({3}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26509
findAllTopFilteredSystemTags failed because of invalid arguments passed in to the method:userId({0}), filter({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26510
findAllTopFilteredPersonalTags failed because of invalid arguments passed in to the method: userId ({0}), filter ({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26511
findSystemTags failed because of invalid arguments passed in to the method: userId ({0}), filter ({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26512
findRelatedSystemTagsByTag failed because of invalid arguments passed in to the method: userId ({0}), tagWords ({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26513
findRelatedSystemTags failed because of invalid arguments passed in to the method: serviceId ({0}), resourceId({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26514
findRecommendedTags failed because of invalid arguments passed in to the method: serviceId ({0}), resourceId ({1}), userId ({2}), count ({3}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26515
deleteTag failed because of invalid arguments passed in to the method: tag ({0}).

Category:
Other

Cause:
One of the input arguments is invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26516
deletePersonalTags failed because of invalid arguments passed in to the method: userId ({0}), tagWord ({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26517
renamePersonalTags failed because of invalid arguments passed in to the method: userId ({0}), oldTagWord ({1}) newTagWord({2}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26518
renamePersonalTags failed because of invalid arguments passed in to the method: userId ({0}), tagWord ({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26519
getTagsByName failed because of invalid arguments passed in to the method: userId ({0}), tagWord ({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26520
lookupResource failed because of invalid arguments passed in to the method: serviceId ({0}), resourceId({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26521
createNewResource failed because of invalid arguments passed in to the method: serviceId ({0}), resourceId ({1}), resource name ({2}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26522
findFilteredPersonalResource failed because of invalid arguments passed in to the method: userId ({0}), filter ({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26523
findSystemResources failed because of invalid arguments passed in to the method: userId ({0}), userFilters ({1}), tagFilters ({2}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26524
findPersonalResources failed because of invalid arguments passed in to the method: userId ({0}), userFilters ({1}), tagFilters ({2}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26525
findRelatedSystemResources failed because of invalid arguments passed in to the method: serviceId ({0}), resourceId ({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26526
findRelatedUsers failed because of invalid arguments passed in to the method: serviceId ({0}), resourceId ({1}).

Category:
Other

Cause:
One of the input arguments is invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26527
findRelatedUsersByTag failed because of invalid arguments passed in to the method: userId({0}), tagWords ({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26528
createNewBookmark failed because of invalid arguments passed in to the method: userId ({0}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26529
lookupBookmark failed because of invalid arguments passed in to the method: serviceId ({0}), resourceId ({1}, userId ({2}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26530
saveBookmark failed because of invalid arguments passed in to the method: bookmark ({0}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26531
deleteBookmark failed because of invalid arguments passed in to the method: bookmark ({0}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26532
A bookmark has been updated at the same time.

Category:
Other

Cause:
There was a concurrent update on the bookmarks.

Action:
Ask user to retry the operation.

WCS-26533
A database exception was thrown (for example., Unique Key constraint violation error).

Category:
Other

Cause:
Tried to insert a duplicate object.

Action:
Retry the action.

WCS-26534
Resource can not be displayed because the service with ID {0} is not found in the Service Registry.

Category:
Other

Cause:
Service definition is not found in Service Registry.

Action:
Please register the service in Service Registry

WCS-26535
Tags service is not available due to {0}.

Category:
Other

Cause:
Check the cause specified in the message.

Action:
Act appropriately to reverse the cause.

WCS-26536
Resource can not be displayed because the authorizerClass {0} is not found.

Category:
Other

Cause:
Class specified by authorizerClass is not found.

Action:
Check the class path of the application to verify inclusion of the authorizerClass.

WCS-26537
findPopularTags failed because of invalid arguments passed in to the method: userId ({0}), order ({1}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26538
findPopularTags failed because of invalid arguments passed in to the method: userId ({0}), serviceId ({1}), resourceId ({2}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26539
findUpdatedResources failed because of invalid arguments passed in to the method: serviceId ({0}), date ({1})).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26540
getTags failed because of invalid arguments passed in to the method: serviceId ({0}), resourceId ({1})).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Make sure that arguments passed in are all valid.

WCS-26541
Error encountered while publishing to activity stream due to {0}.

Category:
Other

Cause:
Error caused by Activity Stream

Action:
Turn on the logging to finest to check the exception detail.

WCS-26542
Error encountered while retrieving user profile due to {0}.

Category:
Other

Cause:
Error caused by Profile server

Action:
Turn on the logging to finest to check the exception detail.

WCS-26543
Error encountered while renaming personal tags.

Category:
Other

Cause:
The creation of the Tagging Service failed or input arguments were invalid

Action:
Turn on the logging to finest to check the exception detail.

WCS-26544
Error encountered while deleting personal tags.

Category:
Other

Cause:
The creation of the Tagging Service failed or input arguments were invalid

Action:
Turn on the logging to finest to check the exception detail.

WCS-26545
Error encountered while finding personal tags.

Category:
Other

Cause:
The creation of the Tagging Service failed or input arguments were invalid

Action:
Turn on the logging to finest to check the exception detail.

WCS-26546
Error encountered while finding personal resources.

Category:
Other

Cause:
The creation of the Tagging Service failed or input arguments were invalid

Action:
Turn on the logging to finest to check the exception detail.

WCS-26547
saveBookmark callback failed for service {0}.

Category:
Other

Cause:
The specified service encountered an internal error.

Action:
Make sure that the service is configured correctly and that arguments passed in are all valid.

WCS-26548
service-definition.xml requires a resource-type element and one or more object-type elements.

Category:
Other

Cause:
The service-definition.xml does not have the appropriate components.

Action:
Add a resource-type and an object type to the service-definition.xml

WCS-26601
No service ID or resource ID - cannot perform {0}.

Category:
Other

Cause:
The consumption of the EditBookmarkBean from the view layer did not pass in the service or the resource IDs necessary.

Action:
Check the view layer to make sure that the resourceId and the serviceId parameters are passed into the page flow scope.

WCS-26602
Cannot create a recommended list because the Tags service cannot be created.

Category:
Other

Cause:
The creation of the Tags service was unsuccessful, so the recommended list could not be created.

Action:
Check for /META-INF/tagging-class-config.properties and verify that a correct accessible class is specified.

WCS-26603
Bookmark cannot be loaded because Tags service cannot be created.

Category:
Other

Cause:
The creation of the Tags service was unsuccessful, so the bookmark object could not be created.

Action:
Check for /META-INF/tagging-class-config.properties and verify that a correct accessible class is specified.

WCS-26604
Bookmark saving failed because a Tags service cannot be created.

Category:
Other

Cause:
The creation of the Tags service was unsuccessful, so the bookmark could not be saved.

Action:
Check for /META-INF/tagging-class-config.properties and verify that a correct accessible class is specified.

WCS-26605
lookupBookmark failed because of invalid arguments passed in to the method: service ID ({0}), resource ID ({1}), and user ID ({2}).

Category:
Other

Cause:
One of the input arguments to lookupBookmark was invalid.

Action:
Make sure that arguments passed in to lookupBookmark are all valid.

WCS-26606
createBookmark failed because of invalid arguments passed in to the method: service ID ({0}), resource ID ({1}), resource name ({2}), and user ID ({3}).

Category:
Other

Cause:
One of the input arguments to createBookmark was invalid.

Action:
Make sure that arguments passed in to createBookmark are all valid.

WCS-26607
findRecommendedTags failed because of invalid arguments passed in to the method: service ID ({0}), resource ID ({1}), and user ID ({2}).

Category:
Other

Cause:
One of the input arguments to findRecommendedTags was invalid.

Action:
Make sure that arguments passed in to findRecommendedTags are all valid.

WCS-26608
This item has been tagged by the same user at the same time. Re-apply your changes.

Category:
Other

Cause:
Concurrent update on the bookmarks.

Action:
Retry the action.

WCS-26609
Some items whose tags are to be renamed have been updated at the same time. Re-apply your changes.

Category:
Other

Cause:
Concurrent update on the bookmarks.

Action:
Retry the action.

WCS-26610
Some items whose tags are to be deleted have been updated at the same time. Re-apply your changes.

Category:
Other

Cause:
Concurrent update on the bookmarks.

Action:
Retry the action

WCS-26611
Tagging Button or Tagging Menu Item will not be rendered because the region "tagging-launch-dialog" is not included in the page.

Category:
Other

Cause:
While building the page, the tagging button was added without adding a corresponding popup task flow.

Action:
Check to make sure the "tagging-launch-dialog" region is indeed included in the page.

WCS-26612
The tagging component "{0}" was not rendered because the underlying Tags service was not available.

Category:
Other

Cause:
The underlying Tags service was not available.

Action:
Look for the errors causing the underlying Tags service to not be available and fix them.

WCS-26613
Error encountered while renaming personal tags.

Category:
Other

Cause:
The creation of the Tagging Service failed or input arguments were invalid

Action:
Turn on the logging to finest to check the exception detail.

WCS-26614
Error encountered while deleting personal tags.

Category:
Other

Cause:
The creation of the Tagging Service failed or input arguments were invalid

Action:
Turn on the logging to finest to check the exception detail.

WCS-26615
Error encountered while finding personal tags.

Category:
Other

Cause:
The creation of the Tagging Service failed or input arguments were invalid

Action:
Turn on the logging to finest to check the exception detail.

WCS-26616
Error encountered while finding personal resources.

Category:
Other

Cause:
The creation of the Tagging Service failed or input arguments were invalid

Action:
Turn on the logging to finest to check the exception detail.

WCS-26617
Error encountered while updating resource with serviceId: {0} resourceId:{1} and resourceName:{2}.

Category:
Other

Cause:
There was a problem saving the updated resource.

Action:
Turn on the logging to finest to check the exception detail.

WCS-26618
This item has been deleted by another user while being tagged. Refresh this page.

Category:
Other

Cause:
Resource was deleted while being tagged.

Action:
Retry the action.

WCS-26621
EncodeBegin error for TaggingPopup tag

Category:
Other

Cause:
Catastrophic error

Action:
Contact Oracle Support Services.

WCS-26622
Error in Tagging Button tag usage - component {0} has attribute {1} whose value is {2}.

Category:
Other

Cause:
The attribute mentioned in the error cannot be null, but no value was found for this attribute.

Action:
Correct your tag usage.

WCS-26623
Component {0} does not support client listeners.

Category:
Other

Cause:
Tried to add a client listener to a component that does not support client listeners.

Action:
Contact Oracle Support Services.

WCS-26701
Could not determine if primary search configuration is Elasticsearch.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26702
Invalid query string {0}, returning empty results.

Category:
Other

Cause:
The query string for searching is probably empty or null.

Action:
Ensure you give a valid search query string.

WCS-26703
Invalid JSON query format {0}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26704
Invalid Search Response {0} for query {1} to url {2}.

Category:
Other

Cause:
Review the response received and determine the cause.

Action:
Take action based on the response received.

WCS-26705
Connection failure while obtaining search result.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26706
Unsupported search facet {0}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26707
Could not obtain search provider factory.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26708
Crawl failed for service {0}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26709
No records to crawl for service {0}.

Category:
Other

Cause:
There is no data to crawl for the given service.

Action:
No action required. If the service does have some data, then review the logs for any other exceptions that might explain why service data is not getting crawled.

WCS-26710
Could not determine last crawled time for service {0} while performing partial crawl, performing full crawl therefore.

Category:
Other

Cause:
Full crawl has not been run on service data yet.

Action:
Full crawl needs to be performed before partial crawl.

WCS-26711
Invalid Crawl source {0}.

Category:
Other

Cause:
Crawling not supported for the given source.

Action:
Contact Oracle Support Services.

WCS-26712
Type and mapping creation failed for service {0} with response {1}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26713
Elasticsearch is not configured, crawl no-op for type {0}.

Category:
Other

Cause:
Elasticsearch is not configured.

Action:
Ensure you have configured Elasticsearch for the application.

WCS-26714
No new entries to crawl for service {0}.

Category:
Other

Cause:
There are no items to crawl for the service.

Action:
This is expected if there are no items available for crawl. If on the contrary, there are artifacts pertaining to this service, then try scheduling crawl again.

WCS-26715
Failure to set last crawled time for service {0} due to {1}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Take action based on the underlying exception.

WCS-26716
Error occurred while obtaining MBean server connection.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26717
Crawler source is null.

Category:
Other

Cause:
The crawler source object passed is null.

Action:
Ensure that you have passed non-null object.

WCS-26718
Crawler source type is null.

Category:
Other

Cause:
The crawler source type object passed is null.

Action:
Ensure that you have passed non-null object.

WCS-26719
Error occurred while obtaining the details of external application connection {0}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26720
Error occurred while obtaining external application connections.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26721
Error occurred while creating external application connection {0}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26722
Error occurred while saving external application connection {0}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26723
Error occurred while looking up external application connection {0}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26724
Error occurred while editing external application connection {0}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26725
Error occurred while setting credentials for external application connection.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26726
Crawler schedule is null.

Category:
Other

Cause:
The crawler schedule object passed is null.

Action:
Ensure that you have passed non-null object.

WCS-26727
Error occurred while creating/updating the crawler schedule for source: {0}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26728
Error occurred while updating crawler schedule for source: {0}, status: {1}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26729
Crawler schedule not found for source: {0}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26730
Error occurred while executing the crawler for type: {0}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26731
Error occurred while enabling crawler source: {0}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26732
Error occurred while getting crawler schedule for source: {0}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Contact Oracle Support Services.

WCS-26733
Crawler is already executing for source: {0}.

Category:
Other

Cause:
Trying to perform an operation which is not supported while crawler is executing.

Action:
Ensure that you perform the operation once the crawler execution is complete.

WCS-26734
Create Mapping failed for type {0} due to {1}. Original request sent to url {2} was {3}.

Category:
Other

Cause:
Creating mapping in Elasticsearch failed due to reason mentioned.

Action:
Review the cause and take action based on that. Run crawl again.

WCS-26735
Search connection configured is not of type Elasticsearch. Unexpected response {0} received.

Category:
Other

Cause:
Unexpected response received while trying to determine if search connection configured is elastic.

Action:
If your search is SES based, ignore this warning. Otherwise review the cause and take action based on that. Restart the Portal Server afterwards.

WCS-26736
Primary Search Connection URL {0} or index {1} not configured.

Category:
Other

Cause:
Search connection URL or search index is not configured

Action:
Configure the search connection and properties and retry.

WCS-26737
Error occurred while trying to fetch search attributes for service {1}

Category:
Other

Cause:
Review the underlying exception for the cause

Action:
Take action based on the underlying exception

WCS-26738
Error occurred while trying to fetch all search attributes configured

Category:
Other

Cause:
Review the underlying exception for the cause

Action:
Take action based on the underlying exception

WCS-26739
Search Attribute {0} was found to be different to {1}. Search Attributes with same name cannot be different.

Category:
Other

Cause:
Search Attributes with same name cannot be different.

Action:
Follow documentation and ensure that search attributes with same name are similar in their attributes.

WCS-26740
Attribute {0} is missing in the configured search attributes for service {1}

Category:
Other

Cause:
Search Attribute is missing in the search-service-attributes.xml which is used to create Elasticsearch mappings and to display custom attributes in search screens.

Action:
Follow documentation and add the missing attribute in the MDS repository.

WCS-26741
Exception while fetching user attributes for Discussions for user: {0}.

Category:
Other

Cause:
Could not fetch Security Attributes from Discussions Crawler Schema.

Action:
Could not fetch Security Attributes.

WCS-26742
Discussions Service is not configured.

Category:
Other

Cause:
Discussions Service is not configured.

Action:
Discussions Service is not configured.

WCS-26743
Exception while fetching partial crawl data.

Category:
Other

Cause:
Failed to parse last crawl time : {0}.

Action:
Could not fetch data for partial crawl.

WCS-26744
Failed to create Elasticsearch index: {0}. Request made : {1}; Response code: {2}; Response data: {3}

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26745
Authorization error while creating Elasticsearch index: {0}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26746
Error occurred while creating Elasticsearch index: {0}. Response code: {1}. Response data: {2}

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26747
Could not create elastic search index for source {0}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26748
Deleting index failed for {0} due to {1}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26749
Index {0} already exists, therefore not creating it.

Category:
Other

Cause:
The index already exists.

Action:
Specify a different alias. If you wish to recreate the index, then delete the said index and retry.

WCS-26750
Failed to create Extractor pipeline in Elasticsearch due to {0}. Original Request: {1}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26751
Authorization error while creating Extractor Pipeline in Elasticsearch.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26752
Error occurred while creating Extractor Pipeline in Elasticsearch: {0}. Response code: {1}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26753
Error while getting calendar instance from date.

Category:
Other

Cause:
Either given date or time is invalid.

Action:
No action is necessary; this is just a diagnostic message.

WCS-26754
Get attribute {0} failed with error {1}.

Category:
Other

Cause:
The attribute value is null or invalid.

Action:
No action is necessary; this is just a diagnostic message.

WCS-26755
Bulk Index call failed for service {0} with status {1} and response {2}

Category:
Other

Cause:
Review the status to determine the cause. Alternatively turn on debug logging.

Action:
Take action based on the underlying cause.

WCS-26756
REST call to crawl url {0} failed for service {1} with status {2} and response {3}

Category:
Other

Cause:
Review the status to determine the cause. Alternatively turn on debug logging.

Action:
Take action based on the underlying cause.

WCS-26757
Incorrect data format received from crawl url {0} for service {1}. Expected {2}, got {3}

Category:
Other

Cause:
Review the crawl url and the parameters passed to it.

Action:
Ensure the url stated returns the data in the specified format

WCS-26758
Error while processing control feed for service {0} during crawl

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26759
Unexpected service {0} tagged for exclusion during crawl, will not be honoured

Category:
Other

Cause:
The excludedServiceIds specified in Portal Crawl URL contains an unsupported service id. The supported ones are oracle.webcenter.community, oracle.webcenter.page, oracle.webcenter.list and oracle.webcenter.peopleconnections.profile

Action:
Review the excludedServiceIds specified in Portal Crawl URL

WCS-26760
Error while trying to determine excluded service ids in portal crawl, all services will be included by default

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26761
Failure to get last crawled time for service {0} due to {1}.

Category:
Other

Cause:
Review the underlying exception for the cause.

Action:
Take action based on the underlying exception.

WCS-26762
Bulk Index Request to url {0} resulted in failure: {1}.

Category:
Other

Cause:
Review the crawl failure message for underlying cause.

Action:
Take action based on the underlying cause.

WCS-26763
Crawler {0} was still executing when server was restarted, therefore setting it to failed.

Category:
Other

Cause:
The Crawler was still executing when the server was restarted. The process was halted and therefore marked failed.

Action:
Schedule or invoke another crawl as per your needs.

WCS-26764
Bulk indexing failed for record {0}.

Category:
Other

Cause:
See the log message for the reason for failure.

Action:
Take action based on the failure and invoke another crawl.

WCS-26765
Fetching data feed for crawl url {0} resulted in failure, trying another time. Status = {1}, Message = {2}

Category:
Other

Cause:
See the log message for the reason for failure.

Action:
No action required, we are attempting the request again.

WCS-26766
Fetching data feed for service {0} crawl url {1} resulted in failure, this data will not be crawled.

Category:
Other

Cause:
See the underlying exception for the reason for failure.

Action:
Take action based on the failure and invoke another crawl.

WCS-26767
Crawler is disabled for source: {0}.

Category:
Other

Cause:
Trying to perform an operation which is not supported while crawler is disabled.

Action:
Ensure that you perform the operation once the crawler is enabled.

WCS-26768
Facet creation of {0} failed due to {1}

Category:
Other

Cause:
Review the facet creation message for underlying cause.

Action:
Take action based on the underlying cause.

WCS-26769
Facet updation of {0} failed due to {1}

Category:
Other

Cause:
Review the facet updation message for underlying cause.

Action:
Take action based on the underlying cause.

WCS-26770
Facet deletion of {0} failed due to {1}

Category:
Other

Cause:
Review the facet deletion message for underlying cause.

Action:
Take action based on the underlying cause.

WCS-26771
Fetching Facets failed due to {0}

Category:
Other

Cause:
Review the facet fetch failure message for underlying cause.

Action:
Take action based on the underlying cause.

WCS-26772
Failed to update the alias {0} with the index {1}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26773
The response obtained is not a valid JSON format, reason: {0}

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26774
Update Mapping failed for type {0} due to {1}. Original request sent to url {2} was {3}.

Category:
Other

Cause:
Update mapping in Elasticsearch failed due to reason mentioned.

Action:
Review the cause and take action based on that. Run crawl again.

WCS-26775
Error while reading the value for property: {0} from MDS, reason: {1}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying cause.

WCS-26776
The configured value for property 'query_string' is not a valid JSON. Value: {0}, failure reason: {1}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying cause.

WCS-26777
Unexpected error occured while fetching the metadata of the files to be excluded in search due to {0}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying cause.

WCS-26778
Unexpected error occured while fetching the metadata of the files to mime type mapping due to {0}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying cause.

WCS-26779
Reindex failed for service {0} with response {1}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-26780
Reindex failed for record {0}; cause: {1}, status code {2}.

Category:
Other

Cause:
See the log message for the reason for failure.

Action:
Take action based on the failure and invoke reindex again.

WCS-26781
Failed to validate Elasticsearch admin user credentials for {0} due to {1}.

Category:
Other

Cause:
Review the underlying exception to determine the cause.

Action:
Take action based on the underlying exception.

WCS-35006
cannot load metadata from XML node

Category:
Other

Cause:
The content of the data-control file (.dcx) might be invalid.

Action:
Verify that the content in the data-control file (.dcx) is valid.

WCS-35008
Login failed.

Category:
Other

Cause:
The specified user credentials were invalid.

Action:
Provide valid user credentials.

WCS-35013
missing method parameters

Category:
Other

Cause:
The data-control operation was invoked without any parameters.

Action:
Contact Oracle Support Services.

WCS-35016
Retrieving data-control definition from runtime data-control object returned null.

Category:
Other

Cause:
The ADF framework did not set the data-control definition within the runtime data control.

Action:
Contact Oracle Support Services.

WCS-35300
Parameters for the operation are missing.

Category:
Other

Cause:
The ADF framework passed a null parameter map to the data-control operation.

Action:
Contact Oracle Support Services.

WCS-35301
The path parameter is not correct.

Category:
Other

Cause:
The path string that was specified was not a valid JCR repository path.

Action:
Verify that the specified path string is a valid path in the content repository, and that it starts with /.

WCS-35302
The type parameter is not correct.

Category:
Other

Cause:
The type string that was specified was not a valid node type in the JCR repository.

Action:
Make sure the type specified is valid in the content repository on which the data control is based. Both the prefix and the local name should be valid. For example, nt:file and nt:folder are valid types.

WCS-35303
cannot generate XPath query

Category:
Other

Cause:
The parameters that were given in the search operation could not be resolved into a valid XPath query string using the content repository session.

Action:
Ensure the attribute names and prefixes used in the parameters are valid and registered in the JCR repository.

WCS-35304
incorrect attribute {0} specified in the predicate

Category:
Other

Cause:
The specified attribute was not found in the repository.

Action:
Provide a valid attribute name.

WCS-35305
incorrect prefix for the attribute {0} in the predicate

Category:
Other

Cause:
The namespace that was used in the attribute was not correct or not registered in the JCR repository.

Action:
Provide a valid prefix, or report the problem to the provider of the JCR adapter used with the repository.

WCS-35306
cannot resolve attribute {0} using the repository session

Category:
Other

Cause:
An invalid attribute or an unregistered prefix was used in the JCR session.

Action:
Provide a valid attribute name in the JCR repository session.

WCS-35307
operator {0} not supported

Category:
Other

Cause:
An invalid operator was specified.

Action:
Specify a valid operator.

WCS-35309
The XPath query {0} is not supported by the JCR adapter.

Category:
Other

Cause:
The JCR adapter might not have been compliant with the XPath support that is required to work with the Content Repository data control.

Action:
Verify that the XPath query is supported by this JCR adapter.

WCS-35310
error in the JCR repository

Category:
Other

Cause:
An error occurred in the JCR adapter.

Action:
Check the exception's cause and JCR adapter's error log.

WCS-35311
error getting the item's URL

Category:
Other

Cause:
An error occurred while generating the URL for an item.

Action:
Contact Oracle Support Services.

WCS-35312
invalid return attribute name {0}

Category:
Other

Cause:
An invalid Java name was entered. The name of a return attribute must be a valid Java name and must be different from "name", "URL", "path" and "primaryType".

Action:
Verify that the attribute name is valid and is not "name", "URL", "path" and "primaryType".

WCS-35313
invalid return attribute type

Category:
Other

Cause:
An invalid return attribute type was specified. Return attributes must be one of the following JCR types: Boolean, Integer, Double, String, or Date.

Action:
Specify a valid return attribute type.

WCS-35314
cannot get value for attribute {0}

Category:
Other

Cause:
The value for the specified attribute could not be retrieved from the JCR node.

Action:
Verify that the JCR path for the attribute is correct.

WCS-35501
No repository was set in the environment.

Category:
Other

Cause:
No repository was specified for this resource.

Action:
Specify a repository to use in creating the resource.

WCS-35502
could not log on to the content repository

Category:
Other

Cause:
There was a problem logging on to the content repository.

Action:
Verify that the connection and credentials are defined correctly and that the repository is accessible.

WCS-35503
An error occurred while accessing the content repository.

Category:
Other

Cause:
There was a problem accessing the content repository.

Action:
Verify that the content repository is accessible.

WCS-35504
An error occurred while trying to close the connection.

Category:
Other

Cause:
Could not close the content repository connection.

Action:
Verify that the connection is still available, and try to close it again.

WCS-35505
Item {0} is not a file or folder.

Category:
Other

Cause:
An item was specified that is not a file or folder.

Action:
Specify an item that is either a file or a folder.

WCS-35506
Item {0} does not exist.

Category:
Other

Cause:
An item was specified that does not exist.

Action:
Verify that the specified item exists.

WCS-35507
unknown control type: {0}

Category:
Other

Cause:
An unknown control type was specified.

Action:
Specify a known control type.

WCS-35508
{0} does not name a ContentDirContext.

Category:
Other

Cause:
An item was specified that is not a ContentDirContext.

Action:
Verify that the item specified is a ContentDirContext.

WCS-35509
invalid search operation: {0}

Category:
Other

Cause:
An unrecognized search operation was specified.

Action:
Use only recognized search operations.

WCS-35510
unable to generate schema

Category:
Other

Cause:
An error occurred while adding attributes to the schema.

Action:
Make sure the schema attributes are defined properly and are not already bound.

WCS-35511
unable to create DataFlavor

Category:
Other

Cause:
An error occurred while trying to create a DataFlavor from the given MIME type.

Action:
Make sure the MIME type is valid and non-null, and that any referenced classes can be loaded.

WCS-35513
unable to create TaskFlowDescriptor

Category:
Other

Cause:
An error occurred while trying to create a TaskFlowDescriptor object.

Action:
Make sure the required classes are in the classpath.

WCS-35514
This feature is only available in a design environment.

Category:
Other

Cause:
A call to a design time only feature was made from run time.

Action:
Do not call this method from run time code.

WCS-35515
Error getting information for connection {0}. The connection will be skipped in the resource catalog.

Category:
Other

Cause:

Action:

WCS-35516
This factory cannot be used at design time.

Category:
Other

Cause:

Action:

WCS-35517
Not a valid content URL: {0}

Category:
Other

Cause:

Action:

WCS-35518
Error getting information for node ID {0}. This node will be skipped in the resource catalog.

Category:
Other

Cause:

Action:

WCS-35900
Illegal value state, cannot read a value previously streamed.

Category:
Other

Cause:
The application mixed calls to getStream() and other get* accessors on the same value object.

Action:
Verify your application code.

WCS-35901
Illegal value state, cannot stream a value previously read.

Category:
Other

Cause:
The application mixed calls to getStream() and other get* accessors on the same value object.

Action:
Verify your application code.

WCS-35902
Error in value conversion (source type = {0}, target type = {1}).

Category:
Other

Cause:
The JCR values could not be converted to the specified type; the source and target type may not be compatible.

Action:
Verify the value conversion rules defined in the JCR specification.

WCS-35903
Error in value conversion (invalid ISO8601 string).

Category:
Other

Cause:
The specified string was not a valid ISO8601 string as specified by JCR and therefore could not be converted to a date.

Action:
Verify the format of the date string.

WCS-35904
Cannot create REFERENCE values.

Category:
Other

Cause:
Values of type REFERENCE are not supported by this JCR repository.

Action:
Avoid using properties of type REFERENCE in your application.

WCS-35905
Input/Output error while reading the binary stream.

Category:
Other

Cause:
The data for the binary property could not be accessed.

Action:
Verify that the storage medium for the JCR repository is accessible.

WCS-35906
UTF8 encoding not supported on this JVM

Category:
Other

Cause:
The JVM does not support UTF-8 encoding.

Action:
Use a supported Java 5 compliant JVM.

WCS-35907
This iterator does not contain any more elements.

Category:
Other

Cause:
The iterator has exhausted all its elements.

Action:
Check the usage of the RangeIterator by your application.

WCS-35908
This iterator does not support the remove operation.

Category:
Other

Cause:
The remove() operation is not supported on this iterator.

Action:
Avoid making calls to RangeIterator#remove() in your application.

WCS-35909
The item at path {0} is not a node.

Category:
Other

Cause:
An item was found at the specified path but it was not a node.

Action:
Check that your application is specifying the correct path.

WCS-35910
"{0}" is not a known namespace prefix.

Category:
Other

Cause:
The name or path contained a namespace prefix unknown to this repository.

Action:
Check the namespace mappings in the current session.

WCS-35911
"{0}" is not a known namespace URI.

Category:
Other

Cause:
The repository did not recognize the specified namespace URI.

Action:
Check the set of namespaces allowed by the current repository.

WCS-35912
The prefix "{0}" is already used.

Category:
Other

Cause:
The specified prefix was already mapped to a namespace and could not be remapped.

Action:
Change the prefix mapping for the URI associated with that prefix before mapping it to another URI.

WCS-35913
{0} is a reserved namespace prefix and cannot be remapped

Category:
Other

Cause:
The "xml" prefix could not be remapped as it is reserved by JCR.

Action:
Check that your application is not trying to remap the "xml" prefix.

WCS-35914
Namespace prefix remapping is not permitted

Category:
Other

Cause:
Could not remap the namespace as the JCR repository does not permit persistent namespace remapping.

Action:
Use the session for any namespace remapping requirements.

WCS-35915
Invalid JCR name or path: {0}

Category:
Other

Cause:
The name or path specified was not a valid JCR name or path.

Action:
Check that the name or path uses valid namespace prefixes and satisfies the JCR grammar rules for names and paths.

WCS-35916
Cannot append an absolute Path

Category:
Other

Cause:
Could not append an absolute path to the existing path.

Action:
Make sure that the appended path is always relative.

WCS-35918
Unexpected error while accessing node type

Category:
Other

Cause:
An unexpected error occurred while accessing a node type.

Action:
Contact Oracle Support Services.

WCS-35919
No such node type: {0}

Category:
Other

Cause:
The node type specified was unknown to the JCR repository.

Action:
Ensure that your are using correct node types for this repository.

WCS-35920
Not a supported query language: {0}

Category:
Other

Cause:
The query language specified was a not a supported query language; this repository only supports XPath.

Action:
Make sure you use only XPath queries.

WCS-35921
Saved queries are not supported.

Category:
Other

Cause:
Could not save the query as this repository does not support saved queries.

Action:
Ensure that your application does not call unsupported JCR functionality.

WCS-35922
Incorrect XPath expression

Category:
Other

Cause:
Could not recognize the XPath expression specified as it is not supported by this JCR repository.

Action:
Check that your XPath query conforms to the JCR specification.

WCS-35923
XPath expression error: invalid enumeration value.

Category:
Other

Cause:
An internal data structure used an invalid value.

Action:
Contact Oracle Support Services.

WCS-35924
XPath expression error: invalid expression tree.

Category:
Other

Cause:
The XPath expression specified was not recognized as it is not supported by this JCR repository.

Action:
Check that your XPath query conforms to the JCR specification.

WCS-35925
Error while generating XML representation of expression tree

Category:
Other

Cause:
Could not create an XML representation of this expression tree.

Action:
Check the exception stack trace for more details.

WCS-35926
Invalid xpath expression.

Category:
Other

Cause:
The XPath expression specified was not recognized as it is not supported by this JCR repository.

Action:
Check that your XPath query conforms to the JCR specification.

WCS-35927
Invalid qualified name: {0}

Category:
Other

Cause:
The specified XPath expression contained an invalid qualified name.

Action:
Check that your XPath query conforms to the JCR specification.

WCS-35928
Unexpected error during XML export.

Category:
Other

Cause:
There was an XML processing error while performing an XML export operation.

Action:
Check that you are using Oracle XML parser v2.

WCS-35930
Index out of bound while accessing path

Category:
Other

Cause:
The specified index for a path element was not valid.

Action:
Check your use of the path object.

WCS-35988
FOTY0012: argument node does not have a typed value

Category:
Other

Cause:

Action:

WCS-35989
XPST0010: The query uses an axis that is not supported by the query engine.

Category:
Other

Cause:

Action:

WCS-35990
XPST0081: A QName used in the expression contains a namespace prefix that cannot be expanded into a namespace URI by using the statically known namespaces.

Category:
Other

Cause:

Action:

WCS-35991
"{0}" is not a valid expression for use as a search string with jcr:contains().

Category:
Other

Cause:
The specified full text search expression was not a valid argument for jcr:contains().

Action:
Check the full text search expression syntax defined in the JCR specification.

WCS-35992
"{0}" is not a valid expression for use as a search string with jcr:like().

Category:
Other

Cause:
The specified regular expression was not a valid argument for jcr:like().

Action:
Check the regular expression syntax defined in the JCR 1.0 specification.

WCS-35993
This XPath expression contains constructs that are not supported by this query engine.

Category:
Other

Cause:
Could not execute this XPath query as it contained constructs that were not supported by this repository.

Action:
Check that your XPath query conforms to the JCR specification.

WCS-35994
XPTY0004: It is a type error if, during the static analysis phase, an expression is found to have a static type that is not appropriate for the context in which the expression occurs, or during the dynamic evaluation phase, the dynamic type of a value does not match a required type as specified by the matching rules in 2.5.4 SequenceType Matching.

Category:
Other

Cause:

Action:

WCS-35995
XPST0017: It is a static error if the expanded QName and number of arguments in a function call do not match the name and arity of a function signature in the static context.

Category:
Other

Cause:

Action:

WCS-35996
FORG0006: invalid argument type

Category:
Other

Cause:

Action:

WCS-35997
FORG0001: invalid value for cast/constructor

Category:
Other

Cause:

Action:

WCS-35998
XPTY0006: (Not currently used)

Category:
Other

Cause:

Action:

WCS-35999
FONC0001: undefined context item

Category:
Other

Cause:

Action:

WCS-36201
Unable to find Page Definition for the template page.

Category:
Other

Cause:

Action:

WCS-36202
Cannot find page with name "{0}".

Category:
Other

Cause:

Action:

WCS-36203
Failed to create SubPath "{0}".

Category:
Other

Cause:

Action:

WCS-36204
Cannot find Page Definition with name "{0}".

Category:
Other

Cause:

Action:

WCS-36205
Unable to find page with path "{0}".

Category:
Other

Cause:

Action:

WCS-36206
Pages metadata file already exists under the path "{0}".

Category:
Other

Cause:

Action:

WCS-36207
Unable to update DataBindings.cpx to update page usageId.

Category:
Other

Cause:

Action:

WCS-36208
Scope folder "{0}" for rename does not exist.

Category:
Other

Cause:

Action:

WCS-36209
Failed to get Permission class for page "{0}".

Category:
Other

Cause:

Action:

WCS-36210
Failed to get Permission target for page "{0}".

Category:
Other

Cause:

Action:

WCS-36211
Cache is not available.

Category:
Other

Cause:

Action:

WCS-36212
Failed to add pages to cache "{0}".

Category:
Other

Cause:

Action:

WCS-36213
Failed to invalidate cache "{0}".

Category:
Other

Cause:

Action:

WCS-36214
Failed to invalidate cache for scope "{0}".

Category:
Other

Cause:

Action:

WCS-36215
A page with name {0} under path {1} does not exist.

Category:
Other

Cause:

Action:

WCS-36216
Failed to remove the page permissions for "{0}".

Category:
Other

Cause:

Action:

WCS-36217
Failed to create .rdf file for page "{0}".

Category:
Other

Cause:

Action:

WCS-36218
Failed to delete .rdf file "{0}".

Category:
Other

Cause:

Action:

WCS-36301
Unable to find page "{0}" in the Binding Context.

Category:
Other

Cause:
Page objects do not exist in the Binding Context.

Action:
Check if the page in the specified path exists.

WCS-36302
Unable to create a document with name "{0}".

Category:
Other

Cause:
Invalid MO name supplied for creation in MDS.

Action:
Check the name provided for creation of the document and ensure that it is a valid MO name.

WCS-36303
Unable to create a document in path "{0}".

Category:
Other

Cause:
MDS raised an MDS_UNSUPPORTED_UPDATE exception while creating document.

Action:
Check the MDS config to ensure that the path is editable.

WCS-36304
Unable to create a pagedefs directory under the scope "{0}".

Category:
Other

Cause:
MDS raised an exception while creating pagedefs folder.

Action:
Check the MDS config to ensure that the path is editable.

WCS-36305
Unable to delete page "{0}".

Category:
Other

Cause:
MDS raised an exception while deleting the page.

Action:
Check the MDS config to ensure that the path is editable.

WCS-36306
Unable to create metadata for page "{0}".

Category:
Other

Cause:
MDS raised an exception while creating metadata for page.

Action:
The metadata for the page already exists under the scope.

WCS-36307
Unable to copy page "{0}".

Category:
Other

Cause:
MDS raised an exception while copying the page.

Action:
Check the MDS config to ensure that the path is editable.

WCS-36308
Unable to rename scope "{0}" to "{1}".

Category:
Other

Cause:
MDS raised an exception while renaming the pages under the scope.

Action:
Check the MDS config to ensure that the path is editable.

WCS-36309
An unexpected error occurred.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact your system administrator.

WCS-36310
Unable to create a page with the name "{0}".

Category:
Other

Cause:
A page with the same name already exists.

Action:
Change to use a different name.

WCS-36311
PageService object is not an instance of PageServiceImpl.

Category:
Other

Cause:
PageService object is not an instance of PageServiceImpl.

Action:
Create a Page service instance and try again.

WCS-36312
Could not flush changes to MDS. Adding view activity failed.

Category:
Other

Cause:
Could not flush changes to MDS.

Action:
Try to create a new page.

WCS-36313
Unable to find page definition file for page "{0}".

Category:
Other

Cause:
The page definition file does not exist or the page definition path is wrong in the Binding Context file.

Action:
Check if the page definition file exists and make sure its path is correct in the Binding Context file.

WCS-36314
Unable to create a page for now because another page is being created.

Category:
Other

Cause:
Another page is being created and all page metadata is locked.

Action:
Try again.

WCS-36315
The page style is no longer available.

Category:
Other

Cause:
The page style is deleted or hidden.

Action:
Choose another page style.

WCS-36316
Cannot perform the requested operation.

Category:
Other

Cause:
You do not have sufficient privileges to perform the requested operations.

Action:
Ask your administrator to grant you the appropriate privileges and then try again.

WCS-36701
Failed to redirect because the page is not specified.

Category:
Other

Cause:

Action:

WCS-36702
An ADF component with name "{0}" is not found.

Category:
Other

Cause:

Action:

WCS-36703
Failed to redirect because the page is not specified.

Category:
Other

Cause:

Action:

WCS-36704
User {0} already has access to the page.

Category:
Other

Cause:

Action:

WCS-36705
You do not have permission to change page security settings anymore.

Category:
Other

Cause:

Action:

WCS-36706
You do not have permission to change page properties anymore.

Category:
Other

Cause:

Action:

WCS-36707
Failed to save the changes because another page operation was in progress.

Category:
Other

Cause:

Action:

WCS-36708
Failed to instantiate DocSecurityBean.

Category:
Other

Cause:

Action:

WCS-36709
Failed to instantiate PageSecurityManager.

Category:
Other

Cause:

Action:

WCS-36801
Failed to change page permission to "{0}".

Category:
Other

Cause:
An unexpected error occurred when changing page permission.

Action:
Check error stack for details.

WCS-36802
Failed to grant page permission "{0}" to user "{1}".

Category:
Other

Cause:
An unexpected error occurred when granting page permission to a user.

Action:
Check error stack for details.

WCS-36803
Failed to revoke page permission from user "{0}".

Category:
Other

Cause:
An unexpected error occurred when granting page permission to a user.

Action:
Check error stack for details.

WCS-36804
Failed to change page security to default mode.

Category:
Other

Cause:
An unexpected error occurred when changing page security mode.

Action:
Check error stack for details.

WCS-36805
A page named {0} already exists.

Category:
Other

Cause:
A page with the specified name exists.

Action:
Specify a unique name for the page.

WCS-37001
An unexpected error occurred.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-37002
An object of type {0} with this ID ({1}) already exits.

Category:
Other

Cause:
An attempt was made to create an object with an existing ID.

Action:
Use a unique ID to Create the object.

WCS-37003
Configuration invalid.

Category:
Other

Cause:
Either the configuration does not exist or the MDS instance is not specified.

Action:
Specify a valid configuration with a MDS instance.

WCS-37004
The name ({0}) is invalid.

Category:
Other

Cause:
The name specified was not valid.

Action:
Specify a valid name.

WCS-37006
Object modified by another user.

Category:
Other

Cause:
The object has been changed by another user.

Action:
Refresh the object and try again.

WCS-37007
Object of type {0} with ID={1} could not be found.

Category:
Other

Cause:
The ID is invalid.

Action:
Specify a valid object ID.

WCS-37008
Object ({0}) is immutable.

Category:
Other

Cause:
An attempt to change this object was made but this object is currently immutable.

Action:
Either update object to allow changes or perform this operation on another object.

WCS-37009
Method: {1} in class: {0} is invalid.

Category:
Other

Cause:
The specified class.method does not exist or is invalid.

Action:
Check underlying method/property specification.

WCS-37010
{0} is not a valid reference name to MDS.

Category:
Other

Cause:
The name specified is not a valid MDS reference name.

Action:
Correct the name to a valid reference.

WCS-37500
The note no longer exists.

Category:
Other

Cause:
Another user deleted the note.

Action:
Refresh the links to see the latest changes.

WCS-37501
This note has been modified by another user.

Category:
Other

Cause:
Another user modified the note. You can only modify the latest version.

Action:
Refresh the page to see the latest changes.

WCS-38001
An unexpected error occurred.

Category:
Other

Cause:
The cause of this error is unknown.

Action:
Try repeating the action that caused this error.

WCS-38002
Data source ({0}) does not exist.

Category:
Other

Cause:
The specified data source is invalid.

Action:
Specify a valid data source and try again.

WCS-38003
Invalid configuration.

Category:
Other

Cause:
Either the configuration does not exist or MDSInstance is not specified.

Action:
Specify a valid MDS configuration and try again.

WCS-38004
Object ({0}) is immutable.

Category:
Other

Cause:
An attempt to change this object was made but this object is currently immutable.

Action:
Either update the object to allow changes or perform this operation on another object.

WCS-38005
An object of type {0} with ID={1} could not be found.

Category:
Other

Cause:
The object ID is invalid.

Action:
Specify a valid object ID.

WCS-38006
Unable to perform transformation

Category:
Other

Cause:
Transformation input sources were invalid.

Action:
Validate the input sources and try again.

WCS-38007
A search error occurred while searching for lists.

Category:
Other

Cause:
The search parameters were invalid.

Action:
Validate the search parameters and try again.

WCS-38008
An error occurred while configuring the List API.

Category:
Other

Cause:
An invalid List API configuration was specified.

Action:
Specify a valid List API configuration and try again.

WCS-38009
An error occurred while looking up list row data.

Category:
Other

Cause:
The database connection not found.

Action:
Verify that a valid database connection exists and try again.

WCS-38010
A search error occurred while searching the discussion forums.

Category:
Other

Cause:
A connection to the discussion forum service could not be established.

Action:
Validate the discussion forum connection details in connections.xml and try again.

WCS-38011
An error occurred while retrieving recent activity information.

Category:
Other

Cause:
Invalid parameters were passed to the Recent Activity API.

Action:
Validate the API usage and try again.

WCS-38012
A search error occurred while searching the service.

Category:
Other

Cause:
Invalid parameters were passed to the Search API.

Action:
Validate the API usage and try again.

WCS-38013
Unable to instantiate class

Category:
Other

Cause:
An invalid class reference was detected.

Action:
Validate the class usage and try again.

WCS-38014
Illegal access exception while accessing class

Category:
Other

Cause:
An invalid class reference was detected.

Action:
Validate the class usage and try again.

WCS-38015
Unable to find class

Category:
Other

Cause:
An unknown class was referenced.

Action:
Verify the class reference and try again.

WCS-38016
Unable to find 'getEnabledScopes' method in class

Category:
Other

Cause:
Class is missing required method.

Action:
Verify that the method exists and try again.

WCS-38017
Service exception while getting service registry.

Category:
Other

Cause:
Invalid parameters were passed to the Service Registry API.

Action:
Validate the API usage and try again.

WCS-38018
A null stream was returned for the RSS XML

Category:
Other

Cause:

Action:

WCS-38019
Object instance for reading RSS feed is not available

Category:
Other

Cause:

Action:

WCS-38020
Unable to get a HTTP connection object for the URL {0}

Category:
Other

Cause:

Action:

WCS-38021
Null object for the XML document

Category:
Other

Cause:

Action:

WCS-38022
The RSS XML does not have a root element

Category:
Other

Cause:
Invalid XML content detected

Action:
Ensure that the RSS feed URL returns XML conforming to the RSS format

WCS-38023
The root element name of the RSS XML is not rss

Category:
Other

Cause:
The XML content is not RSS XML format compliant.

Action:
Ensure that the XML returned by the feed URL is RSS XML format compliant.

WCS-38024
The root element name of the RSS XML does not have any child elements

Category:
Other

Cause:
The XML content returned by the feed URL is not valid

Action:
Ensure that the XML returned by the feed URL is RSS XML format compliant.

WCS-38025
The XML content returned by the feed URL does not have the channel element

Category:
Other

Cause:
The XML content is not RSS XML format compliant

Action:
Ensure that XML returned by the feed URL is RSS XML format compliant.

WCS-38026
The channel element of the RSS XML does not have any child elements

Category:
Other

Cause:
The XML content returned by the feed URL is invalid

Action:
Ensure that the XML returned by the feed URL is RSS XML format compliant.

WCS-42301
The external application ID {0} found while rendering the credential provisioning page is invalid.

Category:
Configuration

Cause:
The external application being referred was probably deleted.

Action:
Check the configuration of the service that is being accessed and fix up the external application reference.

WCS-42302
No back URL exists in the process scope.

Category:
Configuration

Cause:
The credential provisioning page could not establish the back URL because of the following possible reasons: 1) The page was run either in the standalone mode or as a dialog. 2) There was some unexpected error while setting the back URL in the process scope.

Action:
Ensure you haven't run the credential provisioning page in a standalone mode. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-42303
cannot retrieve the back URL to redirect the credential provisioning page

Category:
Logging

Cause:
An I/O error occurred while trying to obtain the back URL to redirect the credential provisioning page.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-42304
The external application ID is found to be null while rendering the credential provisioning page.

Category:
Configuration

Cause:
The credential provisioning page was probably run standalone, or it was invoked from a portlet added from a producer that was not associated with an external application.

Action:
While running the credential provisioning page, ensure that: 1) It is not run in the standalone mode. 2) It is invoked from the link in portlets added from the producers associated with the external application.

WCS-42305
The page is available only to authenticated users.

Category:
Configuration

Cause:
You had not logged into the application before accessing the external application credential provisioning page.

Action:
Ensure that you have logged in before accessing the external application credential provisioning page.

WCS-42306
cannot initialize credential provisioning page

Category:
Logging

Cause:
An unexpected error occurred while trying to initialize the external application. Review the underlying exception in the logs for exact cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-42307
cannot store credentials of external application {0} for user {1}

Category:
Logging

Cause:
There was an unexpected error while trying to store external application credentials for the user. Review the underlying exception in the logs for exact cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-43001
Unable to find the service with ID "{0}" in the service registry.

Category:
Other

Cause:
Either the service ID is wrong or the corresponding META-INF/service-definition.xml file is not available in the classpath.

Action:
Ensure the service ID is correct and the corresponding META-INF/service-definition.xml file is available in the classpath. Note: service-definition.xml file is mostly available from service libraries (within .jar file) of each service, make sure the required service libraries are in the classpath.

WCS-43002
Cannot add service to the registry with the same ID. Service with ID "{0}" is already registered from source "{1}". Failed to add service read from source "{2}".

Category:
Other

Cause:
Either the service-definition contains a service Id that conflicts with another service definition or the same service library (.jar containing the service-definition.xml) is available from multiple classpath locations.

Action:
Ensure the service ID is correct in the corresponding META-INF/service-definition.xml file. Also ensure the same jar file is not available from multiple classpath locations.

WCS-43003
Failed to parse the service-definition.xml found at location "{0}". Due to : {1}

Category:
Other

Cause:
Either the service-definition.xml does not conform to the schema or its not well-formed xml file or its not readable.

Action:
Verify the corresponding service-definition.xml file conforms to the schema with well-formed xml and read access is set on it.

WCS-43004
ServiceContext resource configuration file "{0}" not found, cannot proceed.

Category:
Other

Cause:
The main configuration file that defines the default implementation of ServiceContext class is missing.

Action:
Contact Oracle Support Services.

WCS-43005
ServiceContext resource configuration file "{0}" found, but the data is missing. Cannot proceed.

Category:
Other

Cause:
The main configuration file that defines the default implementation of ServiceContext class is misconfigured, all the required data is not available in this file.

Action:
Contact Oracle Support Services.

WCS-43006
ServiceContext resource configuration file "{0}" found, but the class defined "{1}" is not an instance of oracle.webcenter.framework.service.ServiceContext.

Category:
Other

Cause:
The main configuration file that defines the default implementation of ServiceContext class is misconfigured, the supplied class is not an instance oracle.webcenter.framework.service.ServiceContext.

Action:
Contact Oracle Support Services.

WCS-43007
service-definition being processed from source location "{0}" does not conform to the schema. Missing "definitions" tag.

Category:
Other

Cause:
This is caused due to wrong configuration of service-definition.xml file.

Action:
Update the corresponding file and ensure it starts with 'definitions' tag with namespace as 'http://xmlns.oracle.com/webcenter/framework/service' (e.g.: <definitions xmlns="http://xmlns.oracle.com/webcenter/framework/service">).

WCS-43008
Required attribute "{0}" missing from tag "{1}".

Category:
Other

Cause:
This is caused when the user is required to set the mandatory attribute for the given tag, but and its not set.

Action:
Modify the appropriate configuration file to and supply the mandatory attribute with corresponding value.

WCS-43009
Attempt to invoke "{0}" method on class "{1}", when its locked.

Category:
Other

Cause:
This class or method is locked and cannot be invoked in the current state.

Action:
Do not invoke methods on this class in a state its not accessible, please check the class documentation for more help.

WCS-43010
Scope object cannot be null.

Category:
Other

Cause:
This is caused when an attempt is made to set scope with null value.

Action:
Supply a valid scope object, or create a scope from ServiceContext.

WCS-43011
Unable to find the "{0}" view definition from service: {1}.

Category:
Other

Cause:
The required view definition is missing from the service-definition file.

Action:
Check the appropriate service-definition.xml file to have an entry of the required view definition. Refer to service documentation for more details.

WCS-43012
Error occurred processing the service-definition.xml file from source location "{0}". Due to: {1}.

Category:
Other

Cause:
Either the service-definition is malformed or does not conform to the schema defined.

Action:
Update the corresponding service-definition.xml with correct details.

WCS-43013
ExtensionRegistry instance found "{0}" for registry Id "{1}", is not an instance of {2} class.

Category:
Other

Cause:
This is caused due to wrong configuration of adf-service-config tag in the adf-config.xml file.

Action:
Check the adf-config.xml file for an entry of adf-service-config tag. Search for extension-registry tag here with ID "oracle.webcenter.framework.service.ServiceRegistry", this tag's registry-class attribute should point to a class that is extending from ServiceRegistry class.

WCS-43014
Either the supplied registry Class "{0}" for extension-registry ID "{1}", is not an instance of oracle.webcenter.framework.service.ExtensionRegistry or the class is not available in the classpath. Please check the adf-config.xml for corresponding configuration details.

Category:
Other

Cause:
This is caused due to wrong configuration of extension-registry in the adf-config.xml file.

Action:
Check the adf-config.xml file for an entry of adf-service-config tag. Search for extension-registry tag and ensure this tag's registry-class attribute point's to a class that is an instance of 'oracle.webcenter.framework.service.ExtensionRegistry' class. Also this class should be available in the classpath, otherwise it will fail to load.

WCS-43015
Unable to find the Extension Registry information in the adf-config for registry ID "{0}". Please check the adf-config.xml for corresponding configuration details.

Category:
Other

Cause:
This is caused due to missing tension-registry in configuration in the adf-config.xml file.

Action:
Contact Oracle Support Services.

WCS-43016
Either the supplied handler Class "{0}" for extension-registry ID "{1}", is not an instance of oracle.webcenter.framework.service.ExtensionHandle or the class is not available in the classpath. Please check the adf-config.xml for corresponding configuration details.

Category:
Other

Cause:
This is caused due to wrong configuration of extension-registry in the adf-config.xml.

Action:
Check the adf-config.xml file for an entry of adf-service-config tag. Search for extension-registry tag and ensure this tag's handler-class attribute point's to a class that is an instance of 'oracle.webcenter.framework.service.ExtensionHandler' class. Also this class should be available in the classpath, otherwise it will fail to load.

WCS-43017
Extension tag name cannot be null or empty value.

Category:
Other

Cause:
Wrong extension configuration, mandatory tag name cannot hold null or empty string.

Action:
Refer to the service framework documentation for details on extension-registry configuration.

WCS-43018
No Extension Registry information available for element type "{0}", with the ServiceRegistry. Please check the adf-config.xml for extension registry configuration details.

Category:
Other

Cause:
This is caused due to missing extension-registry configuration in the adf-config.xml for the specified registry Id.

Action:
Check the adf-config.xml file for an entry of adf-service-config tag. Search for extension-registry tag for the appropriate registry Id that is missing and ensure all the registry details are provided.

WCS-43019
ADFConfig does not contain adf-service-config details. Ensure adf-config.xml file contains adf-service-config tag with namespace : {0}.

Category:
Other

Cause:
This is caused due to missing adf-service-config tag from adf-config.xml file.

Action:
Check the adf-config.xml file for an entry of adf-service-config tag.

WCS-43020
No ADF Config information.

Category:
Configuration

Cause:
ADFConfig could not be acquired, either adf-config.xml file is missing or application is not configured properly.

Action:
>Examine the adf-config.xml file and add or update the WebCenter section.

WCS-43021
No Oracle WebCenter Framework information in adf-config file.

Category:
Configuration

Cause:
The application adf-config.xml was found, but the Oracle WebCenter Framework section could not be read or is missing.

Action:
Examine the adf-config.xml file and add or update the WebCenter section.

WCS-43022
resourceInfoPopup jsp inclusion missing from the page.

Category:
Other

Cause:
The jspx or jsff page containing the rah:resourceActionBehavior tag does not include the inline popup fragment: /oracle/webcenter/framework/service/view/jsf/fragments/resourceInfoPopup.jsff that is required to show resource mini-views.

Action:
If this is a custom usage of rah:resourceActionBehavior, add a jsp:include to the page and a reference to the resourceMiniViewPopup page in the page definition. If this is not a custom usage of rah:resourceActionBehavior, contact Oracle Support Services.

WCS-43023
Could not find component : {0}.

Category:
Other

Cause:
The specified component is missing from the current page.

Action:
If this is a customized jsff or jspx page, verify that the component is included at the correct location.

WCS-43024
The ADF Faces application to be used for WebCenter RAH requests has already been specified as {0} in another web.xml.

Category:
Other

Cause:
Multiple web.xml files in the application ear have been marked as being the web application to use for RAH requests.

Action:
Examine the web.xml files from each war file and remove from all but the web application to be used for handling RAH requests.

WCS-43026
No resource ID found for resource group: {0}.

Category:
Other

Cause:
This error occurs when the resource view does not define corresponding group ID.

Action:
Supply valid resource group ID.

WCS-43027
Failed to generate an absolute URL to a resource view.

Category:
Other

Cause:
A runtime problem occurred whilst generating the absolute URL to a resource view.

Action:
Contact Oracle Support Services.

WCS-43028
Scope with name "{0}" already exists.

Category:
Other

Cause:
This error occurs when user tries to create a scope with a name that is already created. Duplicate scopes are not allowed.

Action:
Chose a different name for the scope.

WCS-43029
Scope with name "{0}" does not exist.

Category:
Other

Cause:
This error occurs when user tries to read a scope with a name that is not created earlier.

Action:
Create the scope with the appropriate name and then access it.

WCS-43030
Could not handle complex element "{0}". Neither element has a class attribute nor any of the ElementTypeResolvers could handle it.

Category:
Other

Cause:
This can occur due to missing extension-registry configuration in the adf-config.xml or there is no set/add method on the corresponding application bean to handle complex node.

Action:
Have a proper extension handler registered for this complex node or have set/add method on the bean with the tag name.

WCS-43031
XML processing error: unable to create instance of the class: {0}. {1}

Category:
Other

Cause:
This can occur due to missing extension-registry configuration in the adf-config.xml or there is no set/add method on the corresponding application bean to handle complex node.

Action:
Have a proper extension handler registered for this complex node or have set/add method on the bean with the tag name.

WCS-43032
Class: {0} does not have set or add method for tag: {1}.

Category:
Other

Cause:
This can occur due to missing extension-registry configuration in the adf-config.xml file or there is no set/add method on the corresponding application bean to handle complex node.

Action:
Have a proper extension handler registered for this complex node or have set/add method on the bean with the tag name.

WCS-43033
An error occurred processing the xml, due to: {0}.

Category:
Other

Cause:
Runtime problem invoking the operation.

Action:
Contact Oracle Support Services.

WCS-43034
Unable to set or get an ADF Preference value.

Category:
Other

Cause:
The ADF Preference service raised an exception whilst initializing, getting or setting a preference value.

Action:
Check MDS classpath includes PreferenceNode.xsd.

WCS-43036
Cannot provide the resource link. No FacesContext and no webapp base URL set.

Category:
Other

Cause:
Unable to build up a URL to WebCenter from outside of the web application.

Action:
Contact Oracle Support Services.

WCS-43038
Unable to find help for the current topic.

Category:
Configuration

Cause:
Either the help system is not setup or it is not accessible.

Action:
Examine the WebCenter Configuration for Help and make sure that Help System is up and running.

WCS-43039
Scope Provider resource configuration file "{0}" not found, cannot proceed.

Category:
Other

Cause:
The main configuration file that defines the default implementation of ScopeMetadataProvider class is missing.

Action:
Contact Oracle Support Services.

WCS-43040
Scope Provider resource configuration file "{0}" found, but the data is missing. Cannot proceed.

Category:
Other

Cause:
The main configuration file that defines the default implementation of ScopeMetadataProvider class is misconfigured, all the required data is not available in this file.

Action:
Contact Oracle Support Services.

WCS-43041
ScopeMetadataProvider resource configuration file "{0}" found, but the class defined "{1}" is not an instance of oracle.webcenter.framework.service.ScopeMetadataProvider.

Category:
Other

Cause:
The main configuration file that defines the default implementation of ScopeMetadataProvider class is misconfigured, the supplied class is not an instance oracle.webcenter.framework.service.ScopeMetadataProvider.

Action:
Contact Oracle Support Services.

WCS-43042
Resource Action not created due to missing attributes.

Category:
Other

Cause:
The Group ID (Service ID) and the Resource ID are not present as f:attribute values in the consuming JSPX page.

Action:
Check the JSPX page where this originated from and make sure you add the groupId and resourceId attributes and that they are not null.

WCS-43043
Failed to load resource action handler class "{0}"; using default.

Category:
Other

Cause:
The resource action handler class specified failed to load.

Action:
Check the classpath to inspect whether this class is available; then check accompanying exceptions in the log to further debug the cause.

WCS-43044
Failed to parse view renderer "{0}" as a valid TaskFlow ID; returning null.

Category:
Other

Cause:
The specified task flow ID cannot be parsed properly.

Action:
Check the value of the view renderer specified and investigate how you arrived at that value.

WCS-43045
Failed to parse view renderer "{0}" as a valid TaskFlow ID; treating it as a View ID instead.

Category:
Other

Cause:
The specified task flow ID cannot be parsed properly.

Action:
Check the META-INF/service-definition.xml of the service to verify whether it is a view ID or a TaskFlow ID by checking the documented syntax of both.

WCS-43046
Can not find the message key {0} in the resource bundle "{1}" (from original bundle: {2}).

Category:
Other

Cause:
The string identified by the given key is not found in the resource bundle.

Action:
If this is a custom resource bundle, add a message with the given key to the resource bundle, otherwise contact Oracle Support Services.

WCS-43047
The JPS Service Locator cannot be obtained.

Category:
Security

Cause:
The error was caused while obtaining the JPS Service Locator. Review the underlying exception in the logs to determine the exact cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-43048
User Principal could not be found for authenticated user.

Category:
Other

Cause:
This indicates an error with the Identity Store, or Java Platform Security setup.

Action:
This is an internal warning. The Administrator needs to verify the Identity Store setup.

WCS-43049
An error occurred reading the Connections Context.

Category:
Other

Cause:
This indicates an error with reading the Connection Context.

Action:
Refer to exception detail. If insufficient details to resolve the issue, then contact Oracle Support Services.

WCS-43050
An error occurred reading a service's configuration.

Category:
Other

Cause:
This indicates an error with reading a service's configuration.

Action:
Refer to exception detail. If insufficient details to resolve the issue, then contact Oracle Support Services.

WCS-43051
cannot access Java Object Cache

Category:
Other

Cause:
An exception occurred while accessing Java object cache.

Action:
Review the exception thrown for more details.

WCS-43052
cannot create userprofile region in Java Object Cache

Category:
Other

Cause:
An exception occurred while creating userprofile region in Java object cache.

Action:
Review the exception thrown for more details.

WCS-43053
cannot destroy userprofile region in Java Object Cache.

Category:
Other

Cause:
An exception occurred while removing userprofile region from Java object cache.

Action:
Review the exception thrown for more details.

WCS-43054
An error occurred while trying to lookup connection {0}.

Category:
Other

Cause:
The name may not have been pointing to a valid connection, or some other error occurred when trying to retrieve the connection object.

Action:
Ensure that the connection defined in connections.xml is valid and that the necessary classes can be loaded.

WCS-43055
Resource can not be displayed because the authorizerClass {0} is not found.

Category:
Other

Cause:
Class specified by authorizerClass is not found.

Action:
Check the class path of the application to verify inclusion of the authorizerClass.

WCS-43056
Database type {0} is not recognized.

Category:
Other

Cause:
WebCenter has been configured with a database platform that is not recognized.

Action:
Ensure that the database platform type is set correctly.

WCS-43057
Error closing entity manager factory

Category:
Other

Cause:
An unexpected exception occurred while closing the entity manager factory.

Action:
Review the exception thrown for more details.

WCS-43058
Could not load LifecycleListener class for "{0}" from the service definition.

Category:
Other

Cause:
An unexpected exception occurred while attempting to access the LifecycleListener.

Action:
Review the exception thrown for more details.

WCS-43059
The WebCenterConfig will be reinitialized. Expected class "{0}", class loader "{1}", parent class loader "{2}". Actual class "{3}", class loader "{4}", parent classLoader "{5}".

Category:
Other

Cause:
This indicates an recoverable error with retrieving the WebCenterConfig.

Action:
No action required.

WCS-43060
The connection named "{0}" cannot be found.

Category:
Other

Cause:
The connection name may be incorrect.

Action:
Ensure that the name matches a connection defined for the application.

WCS-43061
Unable to find the WebCenter data source

Category:
Other

Cause:
The data source may not have been configured or cannot be read.

Action:
Check the configuration of the WebCenter data source.

WCS-43062
Unable to parse link

Category:
Other

Cause:
The link URL or network connection is wrong.

Action:
Check the network connection, proxy setting and the link URL.

WCS-43063
Error retrieving enterprise ID/prefix from ADF Context.

Category:
Other

Cause:

Action:

WCS-43064
The version ({0}) of WebCenter Framework Design Time used to create the Portal application is not the same as the version ({1}) of WebCenter Framework Runtime.

Category:
Other

Cause:

Action:

WCS-43065
The build label ({0}) of WebCenter Framework Design Time used to create the Portal application is not the same as the build label ({1}) of WebCenter Framework Runtime.

Category:
Other

Cause:

Action:

WCS-43067
Error "{1}" getting service with ID "{0}".

Category:
Other

Cause:
An unexpected error occurred getting a service by ID.

Action:
Check the configuration of the WebCenter data source.

WCS-43068
Error "{0}" reading service category configuration.

Category:
Other

Cause:
An unexpected error occurred reading the service category configuration.

Action:
Review the exception thrown for more details.

WCS-43069
WebCenterUserNotFoundWarning: Unable to find user {0}.

Category:
Other

Cause:
User with the given name, unique identifier or distinguished name does not exist in the identity store.

Action:
Ensure the user name, unique identifier or distinguished name is correct.

WCS-43070
Unable to find enterprise role {0}.

Category:
Other

Cause:
Role with the given name does not exist in the identity store.

Action:
Ensure the role name is correct.

WCS-43071
Could not obtain display name for user {0} in locale {1}, will resort to default display name

Category:
Other

Cause:
There was an error trying to fetch locale specific display name from identity store.

Action:
Turn on logging and check the logs for the cause of the exception

WCS-43072
cannot access Coherence Cache

Category:
Other

Cause:
An exception occurred while accessing Coherence cache.

Action:
Review the exception thrown for more details.

WCS-43073
cannot destroy userprofile region in Coherence Cache.

Category:
Other

Cause:
An exception occurred while removing userprofile region from Coherence cache.

Action:
Review the exception thrown for more details.

WCS-43075
Unexpected error occurred while encoding the URL {0} due to {1}.

Category:
Other

Cause:
Unexpected error occurred while encoding the URL.

Action:
Review the exception thrown for more details.

WCS-43076
Unexpected error occurred while decoding the URL {0} due to {1}.

Category:
Other

Cause:
Unexpected error occurred while decoding the URL.

Action:
Review the exception thrown for more details.

WCS-43077
Unexpected error occurred while renaming the document {0} to {1} due to {2}.

Category:
Other

Cause:
Unexpected error occurred while renaming the document.

Action:
Review the exception thrown for more details.

WCS-43078
An error occurred while sanitizing the HTML input

Category:
Other

Cause:
Unexpected error occurred while sanitizing the HTML input

Action:
Review the exception thrown for more details.

WCS-43079
The URL entered is not available in the list of valid URLs.

Category:
Other

Cause:
The URL is invalid

Action:
Contact your system administrator for valid URLs.

WCS-43080
Unexpected error occured while validating the URL due to {0}.

Category:
Other

Cause:
Unexpected error occured while validating the URL

Action:
Review the exception thrown for more details

WCS-43081
An error occurred while trying to fetch custom attribute {0}

Category:
Other

Cause:
Unexpected error occurred while trying to fetch the custom attribute setting

Action:
Review the exception thrown for more details.

WCS-44001
cannot load role provider implementation for service ID: {0}

Category:
Security

Cause:
The provider class configured in role-mapping-metadata tag of the specified service definition was not available to the classloader.

Action:
Ensure that the provider class specified in the service-definition.xml file is available to the classloader.

WCS-44002
The Role Mapping provider encountered an exception while performing security role mapping for service {0}.

Category:
Security

Cause:
This is caused by an error experienced by service-specific Role Mapping provider.

Action:
Inspect the server logs and rectify the problem encountered by the service Role Mapping provider.

WCS-44003
The Role Mapping provider cannot find the service role: {0}. Exception from the provider: {1}.

Category:
Security

Cause:
The Role Mapping provider cannot find the service role. Review the exception from the provider to determine the exact cause.

Action:
Inspect the server logs and rectify the problem encountered by the service Role Mapping provider.

WCS-44004
An internal JPS error occurred while retrieving information from the Application Policy Store.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44005
cannot find security extension in Service Registry for service ID: {0}

Category:
Security

Cause:
No security extension was registered for the given service. Perhaps the service library was not available in the classpath.

Action:
Check the service library is available in the classpath. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44006
There is no mapped service role for the WebCenter Portal role {1} to which the user {0} is assigned.

Category:
Security

Cause:
A user was assigned to a WebCenter Portal role that was not yet mapped to any service role.

Action:
Ensure that the WebCenter Portal role is mapped to a service role.

WCS-44007
An internal JPS error occurred while initializing the Application Policy Store.

Category:
Security

Cause:
The Application Policy Store (jps-config.xml) was probably not configured correctly.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44009
Error obtaining JPS Service instance: {0}.

Category:
Security

Cause:
The value returned for the JPS Service instance was null. This may be caused by configuration error in jps-config.xml.

Action:
Contact Oracle Support Services.

WCS-44010
A JPS error occurred while deleting users from the service ID/service role: {0} / {1}.

Category:
Security

Cause:
The error was caused while accessing the application policy store for deleting users. Review the underlying exception in the logs to determine the exact cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44011
Error getting handle to application policy for application {0}.

Category:
Security

Cause:
Either the application policy is not available or policy store is not configured correctly. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44012
Error getting handle to default policy store.

Category:
Security

Cause:
Either the policy store is not accessible or not configured correctly. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44101
Invalid PeoplePicker Scope {0} passed.

Category:
Configuration

Cause:
The scope is not of the valid type. It can be GLOBAL or SUB_SCOPED

Action:
Pass a valid scope

WCS-44102
Invalid PeoplePicker Scope ID {0} passed.

Category:
Configuration

Cause:
An invalid Scope ID has been passed.

Action:
Ensure a valid scope/community ID is passed.

WCS-44103
Unknown error encountered while selecting user(s) in people picker.

Category:
Security

Cause:
Review the root cause of the exception for more details.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44104
Scope Id is a required parameter for scoped people search.

Category:
Security

Cause:
Scope Id not provided.

Action:
Provide Scope Id.

WCS-44105
And unknown error occurred while trying to validate if user {0} exists

Category:
Security

Cause:
Review the root cause of the exception for more details.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44106
Unknown error encountered while selecting group(s) in group picker.

Category:
Security

Cause:
Review the root cause of the exception for more details.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44107
And unknown error occurred while trying to validate if group {0} exists

Category:
Security

Cause:
Review the root cause of the exception for more details.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44108
The search exceeded the time limit. Check the identity store connection details or refine your search criterion.

Category:
Security

Cause:
The underlying identity store and policy store could be down.

Action:
Check that underlying repositories are accessible. Check logs and contact Oracle Support

WCS-44109
The search exceeded the size limit. Refine your search criterion.

Category:
Security

Cause:
The search results in a large dataset that is not supported by the underlying identity store.

Action:
Refine your search criterion to something more narrow.

WCS-44110
An unexpected error occurred while searching for users/roles. Check logs for further details.

Category:
Security

Cause:
An unexpected error occurred while searching for identities. Consult the underlying cause.

Action:
If the underlying cause does not provide any action, contact Oracle Support.

WCS-44151
An error occurred while retrieving the Identity Store.

Category:
Security

Cause:
This is caused when the Identity Store configured in jps-config.xml is not accessible or is not running. Review the underlying exception in the logs to determine the exact cause.

Action:
Ensure that the Identity Store is configured correctly in jps-config.xml and is running. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44152
An error occurred while sending an e-mail.

Category:
Security

Cause:
The error occurred because the e-mail account or the e-mail service was not configured correctly or the e-mail server was not running.

Action:
Ensure that your e-mail account and the e-mail service are configured properly and the e-mail server is running.

WCS-44153
An error occurred while generating the HMAC token.

Category:
Security

Cause:
The JVM did not support MessageDigest algorithms, such as MD5 or SHA, or the UTF8 encoding.

Action:
Ensure the JVM supports UTF8 encoding and MD5/SHA message digest algorithms. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44154
An error occurred while getting the scope roles for scope ID {0}.

Category:
Security

Cause:
Either the policy store was configured incorrectly or was inaccessible or the scope ID passed was invalid.

Action:
Ensure that the policy store is configured correctly and is running. Also, ensure that the scope ID passed is valid.

WCS-44155
The permission class is null for the service ID: {0}.

Category:
Security

Cause:
The permission class was not defined in the service-definition.xml file.

Action:
Ensure that the permission class is defined in the service-definition.xml file for the service.

WCS-44156
The value of resource bundle is null for the service ID: {0}.

Category:
Security

Cause:
The resource bundle was not defined in the service-definition.xml file.

Action:
Ensure that the resource bundle is defined in the service-definition.xml file.

WCS-44157
The value of permission target is null for the service ID: {0}.

Category:
Security

Cause:
The permission target was not defined in the service-definition.xml file.

Action:
Ensure that the permission target is defined in the service-definition.xml file.

WCS-44158
The value of permission action is not defined for the service ID: {0}.

Category:
Security

Cause:
The permission action (permission-action-list tag) was not defined in the service-definition.xml file.

Action:
Ensure that the permission actions are defined in the service-definition.xml file by using the permission-action-list tag.

WCS-44159
The value of permission admin action is not defined for the service ID: {0}.

Category:
Security

Cause:
The permission admin action (permission-manage-action tag) was not defined in the service-definition.xml file.

Action:
Ensure that the permission admin actions are defined in the service-definition.xml file by using the permission-manage-action tag.

WCS-44160
The role mapping class is not defined for the service ID: {0}.

Category:
Security

Cause:
The role mapping class was not defined in the service-definition.xml file.

Action:
Ensure that the role mapping class is defined in the service-definition.xml file.

WCS-44161
The role mapping resource bundle is not defined for the service ID: {0}.

Category:
Security

Cause:
The role mapping resource bundle was not defined in the service-definition.xml file.

Action:
Ensure that the role mapping resource bundle is defined in the service-definition.xml file.

WCS-44162
Security Extension is not defined for the service ID: {0}.

Category:
Security

Cause:
The Security Extension (security-definition node) was not defined in the service-definition.xml file of the service.

Action:
Ensure that the Security Extension (security-definition node) is properly defined in the service-definition.xml file.

WCS-44163
An error occurred while retrieving service extension definition(service-definition.xml).

Category:
Security

Cause:
The service jars are not correctly packaged or the jars are corrupt.

Action:
Ensure that webcenter framework shared library is correctly defined and the library jars are not corrupt.

WCS-44164
An error occurred while retrieving the spi file .

Category:
Security

Cause:
The are multiple spi files.

Action:
Ensure that only spi file with the name oracle.webcenter.security.selfregistration.custom.SelfRegActionHandlerSpi.properties exists.

WCS-44165
The principal is not of type JpsRole

Category:
Security

Cause:
The principal object passed to the api is not of type JpsRole.

Action:
Ensure that the parameter passed to the api is of type JpsRole.

WCS-44166
Application Policy for {0} does not exist. Creating a new application policy.

Category:
Security

Cause:
The application did not package any policies.

Action:
None as a new policy has been created. However ensure that application did not indeed package any policies and this was not a case of policies not being migrated. Contact Oracle Support in that case.

WCS-44167
Public registration is not enabled for this site.

Category:
Security

Cause:
The public registration option is not enabled.

Action:
Ensure that public registration is enabled in the general tab of Webcenter administration.

WCS-44168
The principal argument is null

Category:
Security

Cause:
The principal object passed to the api is null.

Action:
Ensure that the parameter passed to the api is not null.

WCS-44169
Error while determining security attributes for user {0}

Category:
Security

Cause:
The user {0} passed to determine security attributes does not exist in the underlying identity store.

Action:
Ensure the user name is valid.

WCS-44170
Error occurred while retrieving the security attributes of user {0}

Category:
Security

Cause:
An error occurred while querying the identity store or the policy store to determine the user's security attributes. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-44171
Error occurred while determining security attributes for service {0}

Category:
Security

Cause:
An error occurred while querying the policy store to determine the principals that were granted view access for the given service. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-44172
Error occurred while determining security attributes for service {0} in scope {1}

Category:
Security

Cause:
An error occurred while querying the policy store to determine the principals that were granted view access for the given service and scope. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-44173
Error occurred while determining security attributes for artifact {0} belonging to service {1}

Category:
Security

Cause:
An error occurred while querying the policy store to determine the principals that were granted view access for the given service and artifact. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-44174
Error encountered while getting the HMAC initial key from the credential store

Category:
Security

Cause:
There is a problem while accessing the credential store. Review the underlying exception in the logs to determine the exact cause.

Action:
Ensure the credential store is setup properly. Take action based on the underlying exception details.

WCS-44175
Error occurred while obtaining mapped service {0} roles for WebCenter Portal role {1}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44176
Error occurred while obtaining mapped application roles for service {0} and service role with ID {1} in scope {2}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44177
Error occurred while adding role mapping entry for service {0} and service role {1} to webcenter role {2}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services. This error can be ignored if upgrade is being re-run.

WCS-44178
Error occurred while removing role mapping entry for service {0} and service role {1} from WebCenter Portal role {2}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44179
Error occurred while removing role mapping entries for service {0} in scope {1}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44180
Error occurred while removing role mapping entries for scope {0}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44181
Error occurred while fetching role mapping metadata for scope {0}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44182
Error occurred while adding role mapping metadata to scope {0}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44183
Cannot copy role mapping metadata for scope {0} as the metadata already exists

Category:
Security

Cause:
Role mapping metadata already existed for the given scope.

Action:
Remove the role mapping metadata for the scope and then perform this operation again. Alternatively, you can pass a different scope for which the role mapping metadata does not already exist.

WCS-44184
Error occurred while fetching role mapping metadata for service {0} in scope {1}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44185
Error occurred while adding role mapping metadata for service {0} in scope {1}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44186
Unable to obtain service {0} role mapping metadata for scope {1}

Category:
Security

Cause:
The query to obtain role mapping metadata for the scope returned a path for which the metadata did not exist.

Action:
Ensure the service role mapping metadata exists for the scope.

WCS-44187
The role mapping metadata for service {0} in scope {1} is being modified by another user. Try the operation again after some time.

Category:
Security

Cause:
Another user acquired the write lock on the service role mapping metadata.

Action:
Try the operation after some time.

WCS-44188
Cannot copy the role mapping metadata for service {0} in scope {1}

Category:
Security

Cause:
The service role mapping metadata for the scope already existed.

Action:
Remove the service role mapping for the scope and then perform the operation again. Alternatively, you can pass a different service and scope for which the role mapping metadata does not already exist.

WCS-44189
Cannot find the WebCenter Portal application role {0}

Category:
Security

Cause:
The WebCenter Portal application role passed to Role Manager did not exist.

Action:
Ensure that a valid application role is passed to Role Manager.

WCS-44190
Error copying role mapping metadata from role {0} to role {1} in scope {2}

Category:
Security

Cause:
Role mapping metadata could not be copied. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. To perform role mapping, use the Roles tab in the portal settings.

WCS-44191
Error deleting role mapping metadata from role {0} in scope {1}

Category:
Security

Cause:
The role mapping metadata could not be deleted. Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-44192
Error while determining enterprise role mapping support. Enterprise groups, and not the individual group members, will be added directly as members.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
If a service configured does not support enterprise role mapping, then take action based on the underlying exception details.

WCS-44193
The permission action is invalid for the service ID: {0}.

Category:
Security

Cause:
Either permission action name or icon was not specified in the service-definition.xml file.

Action:
Ensure that the permission action name and icon is defined correctly in the service-definition.xml file for the service. The permission action should be specified as <permission-action name="view" icon="/adf/webcenter/view_qualifier.png"/>

WCS-44194
The application level permission class is null for the service ID: {0}.

Category:
Security

Cause:
The application permission class was not defined in the service-definition.xml file.

Action:
Ensure that the application permission class is defined in the service-definition.xml file for the service. The application permission class should be specified as <application-permission-impl>permission class</application-permission-impl> in <application-permission> node.

WCS-44195
The application level permission target is not defined for the service ID: {0}.

Category:
Security

Cause:
The application permission target was not defined in the service-definition.xml file.

Action:
Ensure that the application permission target is defined in the service-definition.xml file for the service. The application permission target should be specified as <application-permission-target-id>permission target</application-permission-target-id> in <application-permission> node.

WCS-44196
The application level permission actions is not defined for the service ID: {0}.

Category:
Security

Cause:
The application permission actions list was not defined in the service-definition.xml file.

Action:
Ensure that the application permission actions list is defined in the service-definition.xml file for the service. The application permission actions should be specified as <application-permission-action-list>permission actions</application-permission-action-list> in <application-permission> node.

WCS-44197
The scope level permission class is not defined for the service ID: {0}.

Category:
Security

Cause:
The scope permission class was not defined in the service-definition.xml file.

Action:
Ensure that the scope permission class is defined in the service-definition.xml file for the service. The scope permission class should be specified as <scope-permission-impl>permission class</scope-permission-impl> in <scope-permission> node.

WCS-44198
The scope level permission target is not defined for the service ID: {0}.

Category:
Security

Cause:
The scope permission target was not defined in the service-definition.xml file.

Action:
Ensure that the scope permission target is defined in the service-definition.xml file for the service. The scope permission target should be specified as <scope-permission-target-id>permission target</scope-permission-target-id> in <scope-permission> node.

WCS-44199
The scope level permission actions is not defined for the service ID: {0}.

Category:
Security

Cause:
The scope permission actions list was not defined in the service-definition.xml file.

Action:
Ensure that the scope permission actions list is defined in the service-definition.xml file for the service. The scope permission actions should be specified as <scope-permission-action-list>permission actions</scope-permission-action-list> in <scope-permission> node.

WCS-44200
The resource level permission class is not defined for the service ID: {0}.

Category:
Security

Cause:
The resource permission class was not defined in the service-definition.xml file.

Action:
Ensure that the resource permission class is defined in the service-definition.xml file for the service. The resource permission class should be specified as <resource-permission-impl>permission class</resource-permission-impl> in <resource-permission> node.

WCS-44201
The resource level permission target is not defined for the service ID: {0}.

Category:
Security

Cause:
The resource permission target was not defined in the service-definition.xml file.

Action:
Ensure that the resource permission target is defined in the service-definition.xml file for the service. The resource permission target should be specified as <resource-permission-target-id>permission target</resource-permission-target-id> in <resource-permission> node.

WCS-44202
The resource level permission actions is not defined for the service ID: {0}.

Category:
Security

Cause:
The resource permission actions list was not defined in the service-definition.xml file.

Action:
Ensure that the resource permission actions list is defined in the service-definition.xml file for the service. The resource permission actions should be specified as <resource-permission-action-list>permission actions</resource-permission-action-list> in <resource-permission> node.

WCS-44203
The application role operations list is not specified at the application level for the service ID: {0}.

Category:
Security

Cause:
The application role operations list is not specified at the application level. It was not defined in the service-definition.xml file.

Action:
Ensure that the application role operations list is defined at the application level in the service-definition.xml file for the service.

WCS-44204
The application role operations list is not specified at the scope level for the service ID: {0}.

Category:
Security

Cause:
The application role operations list is not specified at the scope level was not defined in the service-definition.xml file.

Action:
Ensure that the application role operations list is defined at the scope level in the service-definition.xml file for the service.

WCS-44205
The application role operations list is not specified at the resource level for the service ID: {0}.

Category:
Security

Cause:
The application role operations list is not specified at the resource level was not defined in the service-definition.xml file.

Action:
Ensure that the application role operations list is defined at the resource level in the service-definition.xml file for the service.

WCS-44206
The application role operation specified is invalid for the service ID: {0}.

Category:
Security

Cause:
Operation name or application role or icon has not been specified correctly for the application role operation in service-definition.xml

Action:
Ensure that the application role operation is specified correctly with operation name, application role and icon in the service-definition.xml file for the service. An application role operation entry looks like this - <application-operation name="manage" approle="AppConnectionManager" icon="/adf/webcenter/manage.png"/>

WCS-44207
Error occurred while adding resource {0} security override entry for service {1} in scope {2}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44208
Error occurred while removing resource {0} security override entry for service {1} in scope {2}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44209
Error occurred while checking if resource {0} override security for service {1} in scope {2}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44210
Error occurred while removing security override entries for scope {0}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44211
Error occurred while removing security override entries for service {0} in scope {1}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44212
The security override metadata for service {0} in scope {1} is being modified by another user. Try the operation again after some time.

Category:
Security

Cause:
Another user acquired the write lock on the service security override metadata.

Action:
Try the operation after some time.

WCS-44213
Invalid Security Handler for service {0}. Expected Type: {1} Actual Type: {2}.

Category:
Security

Cause:
Security Handler defined in service-definition was of incorrect type

Action:
Define the correct security handler in the service-definition as specified

WCS-44214
Security Extension not found for service {0}.

Category:
Security

Cause:
Security Extension not defined in service-definition.

Action:
Define the security extension appropriately in the service-definition.

WCS-44215
Security Handler not found for service {0}.

Category:
Security

Cause:
Security Handler specified in the security extension is either undefined or could not be found.

Action:
Ensure the correct security handler class is defined in the security extension of service-definition.

WCS-44216
Could not determine security authorization type for service {0}. It needs to be one of the following - PERMISSION, APPLICATION_ROLE or ROLEMAPPING.

Category:
Security

Cause:
The security extension either does not contain any authorization model or contains more than one.

Action:
Depending on the authorization model, security extension must be updated to specify the appropriate security model.

WCS-44217
Permission security model not defined at {0} level for service {1}.

Category:
Security

Cause:
Permission check or provisioning is being attempted at specified level where as the security extension in the service-definition does not define given level permission security model

Action:
Either define specified level permission security metadata or do not attempt security provisioning or check at given level for the service.

WCS-44218
Application Roles security model not defined at {0} level for service {1}.

Category:
Security

Cause:
Security check or provisioning is being attempted at specified level where as the security extension in the service-definition does not define given level application role security model

Action:
Either define specified level application role security metadata or do not attempt security provisioning or check at given level for the service.

WCS-44219
Error occurred revoking permissions for {0} service resource {1}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44220
Application Role not defined for {0} service action {1} at {2} level.

Category:
Security

Cause:
Application Role for the given service action and level not defined in security extension of service-definition.

Action:
Define the application role mapping for the given service action at the given level else do not attempt security provisioning or check for the service at given level.

WCS-44221
Error occurred checking {0} action for {1} service at {2} level.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44222
An error occurred while retrieving the policies or permissions.

Category:
Security

Cause:
This is caused when the policy store is not accessible or is not running or the service definition is not defined properly.

Action:
Ensure that the policy store and service definition is configured properly and is running.

WCS-44223
An error occurred while saving the permissions.

Category:
Security

Cause:
This is caused when the policy store is not accessible or is not running or the service definition is not defined properly.

Action:
Ensure that the policy store and service definition is configured properly and is running.

WCS-44224
An error occurred while saving the permissions.

Category:
Security

Cause:
This is caused when the service definition is not defined properly.

Action:
Ensure that the service definition is configured properly.

WCS-44225
An error occurred while setting service id.

Category:
Security

Cause:
This is caused when the service definition is not defined properly.

Action:
Ensure that the service definition is configured properly.

WCS-44226
Error while accessing data from OPSS Policy Store.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44227
An error occurred while getting portal assets and WebCenter Portal services

Category:
Security

Cause:
This is caused when the service definition is not defined properly.

Action:
Ensure that the service definition is configured properly.

WCS-44228
An error occurred while determining list of portal assets that override security for service {0} in scope {1}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-44229
An error encountered while getting mapped action.

Category:
Security

Cause:
This is caused when the service definition is not defined properly.

Action:
Ensure that the service definition is configured properly.

WCS-44230
An error encountered while trying to retrieve {0} service policies at {1} level for scope {2} and asset {3}.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-44231
An error encountered while trying to grant {0} service policies at {1} level for scope {2} and asset {3}.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The grant could already exist.

Action:
Take action based on the underlying exception details. If the grant already exists, revoke the grant using WLST and perform operation again.

WCS-44232
An error encountered while trying to revoke {0} service policies at {1} level for scope {2} and asset {3}.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The grant being revoked probably does not exist.

Action:
Take action based on the underlying exception details.

WCS-44233
An error encountered while trying to obtain subject for user {0}, returning anonymous user subject instead.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause.

Action:
Take action based on the underlying exception details.

WCS-44234
An error encountered while trying to create role {0}.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The role may be already exists or there is a problem with policy store.

Action:
Take action based on the underlying exception details.

WCS-44235
An error encountered while trying to get application roles.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The roles may not exists or there is an issue with the policy store.

Action:
Take action based on the underlying exception details.

WCS-44236
An error encountered while trying to create role {0}.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The role may be already exists or there is a problem with the policy store.

Action:
Take action based on the underlying exception details.

WCS-44237
An error encountered while trying to get members.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The members may not exist or there is a problem with the policy store.

Action:
Take action based on the underlying exception details.

WCS-44238
An error encountered while trying to get members.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The member may not exist or there is a problem with the policy store.

Action:
Take action based on the underlying exception details.

WCS-44239
An error encountered while trying to delete members.

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The member may already exist or there is a problem with the policy store.

Action:
Take action based on the underlying exception details.

WCS-44240
Cannot access the resource

Category:
Security

Cause:
The service was not defined properly.

Action:
Ensure that the service definition is configured properly.

WCS-44241
Failed to issue token.

Category:
Security

Cause:
Trust Service Token Manager failed to issue the token.

Action:
Take action based on the underlying exception details.

WCS-44242
TrustService instance is null.

Category:
Security

Cause:
Failed to get TrustService instance from the JPS context.

Action:
Take action based on the underlying exception details.

WCS-44243
TokenManager instance is null.

Category:
Security

Cause:
Failed to get TokenManager instance from the TrustService.

Action:
Take action based on the underlying exception details.

WCS-44244
Could not execute search

Category:
Security

Cause:
The identity store is not up or is not configured properly.

Action:
Ensure that the identity store is up and configured properly.

WCS-44245
Could not add to role

Category:
Security

Cause:
The policy object already exists or the policy store is not configured properly.

Action:
Ensure that the policy is not already added and policy store is configured properly.

WCS-44246
An internal JPS error occurred while exporting / importing application roles.

Category:
Security

Cause:
This may have been caused when retrieving information from the Application Policy Store or while granting permissions to roles.

Action:
Review the exception to determine exact cause.

WCS-44247
Could not delete application role {0}.

Category:
Security

Cause:
This may have been caused because the role to be deleted does not exist any more.

Action:
Review the exception to determine exact cause.

WCS-44248
The documents role mapping failed during import for portal : {0} and application role {1}.

Category:
Security

Cause:
This is caused by an error experienced by service-specific Role Mapping provider.

Action:
Inspect the server logs and rectify the problem encountered by the service Role Mapping provider.

WCS-44249
No application role found for scope : {0}.

Category:
Security

Cause:
This may be due to an error that could have occurred during Portal creation or import due to which the roles were not created.

Action:
Inspect the logs to confirm which Portal is this error being thrown for and try manually accessing the Portal. If the Portal is inaccessible, re try import or, re create the Portal.

WCS-44250
Unable to obtain MDSSession to initialize {0} store.

Category:
Security

Cause:
This is caused by an underlying MDS Configuration exception while trying to initialize the customization config.

Action:
Review the exception to determine exact cause.

WCS-44251
Start time {0} specified for an impersonation grant cannot be after end time {1}

Category:
Security

Cause:
Start time for impersonation grant is after end time

Action:
Ensure start time specified for an impersonation grant is before end time

WCS-44252
You cannot add, update, or remove yourself as an impersonator

Category:
Security

Cause:
Adding, updating, or removing oneself as an impersonator is not allowed

Action:
Ensure impersonator being added, updated or removed is a valid impersonator

WCS-44253
Impersonator {0} already added for user {1}

Category:
Security

Cause:
You can add an impersonator only once for a user

Action:
Ensure you add an impersonator only once for a user. To specify a different time duration, edit the existing grant

WCS-44254
Impersonatee {0} already added for user {1}

Category:
Security

Cause:
You can add an impersonator only once for a user

Action:
Ensure you add an impersonator only once for a user. To specify a different time duration, edit the existing grant

WCS-44255
Cannot update or delete impersonator {0} for user {1} as impersonator not yet added

Category:
Security

Cause:
The impersonator being updated or deleted has not been added yet

Action:
Ensure the impersonator has been added before trying to update or remove the impersonation grant

WCS-44256
Cannot update or delete impersonatee {0} for user {1} as impersonatee not yet added

Category:
Security

Cause:
The impersonator being updated or deleted has not been added yet

Action:
Ensure the impersonator has been added before trying to update or remove the impersonation grant

WCS-44257
Impersonator user {0} could not be found

Category:
Security

Cause:
The impersonator specified is not a valid user

Action:
Ensure you specify a valid impersonator

WCS-44258
Impersonatee user {0} could not be found

Category:
Security

Cause:
The impersonatee specified is not a valid user

Action:
Ensure you specify a valid impersonatee

WCS-44259
Fetching Impersonator user {0} failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44260
Fetching Impersonatee user {0} failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44261
Adding impersonator {0} for user {1} failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44262
Updating impersonator {0} for user {1} failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44263
Removing impersonator {0} for user {1} failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44264
Getting impersonators for user {0} failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44265
Getting impersonatees for user {0} failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44266
Removing expired impersonation grants for user {0} failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44267
Starting impersonation session for user {0} failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44268
Terminating impersonation session for current user failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44269
User {0} is not a valid impersonator

Category:
Security

Cause:
The user specified as impersonator does not belong to webcenter#-#impersonators role.

Action:
Ensure you specify a user that belongs to webcenter#-#impersontors role.

WCS-44270
Determining if user {0} is a valid impersonator failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44271
Adding or updating impersonator {0} for user {1} failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44272
Searching for impersonators matching pattern {0} failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44273
Impersonation Time delta {0} specified is in invalid format

Category:
Security

Cause:
Time delta specified was not a valid integer

Action:
Check documentation to understand the format in which this delta needs to be specified. It needs to be a valid integer

WCS-44274
Impersonation configuration check failed

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause

Action:
Take action based on the underlying exception details

WCS-44275
End time {0} cannot be before current time.

Category:
Security

Cause:
End time for impersonation grant is before current time

Action:
Ensure end time is not before current time

WCS-44300
An error encountered while granting permissions

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The policy may already have been granted or the identity may not exist or there is a problem with the policy store.

Action:
Take action based on the underlying exception details.

WCS-44301
An error encountered while revoking permissions

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The policy may not exist or the identity may not exist or there is a problem with the policy store.

Action:
Take action based on the underlying exception details.

WCS-44302
An OPSS error occurred while locating the audit service.

Category:
Security

Cause:
The error would be caused when Audit Service is not configured. Review the jps-config.xml configuration file in conjunction with the stack trace if Audit Service needs to be enabled for WebCenter Portal.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-44304
Invalid security attribute {0} obtained for artifact {1} in service {2}

Category:
Security

Cause:
The security attribute returned by the service does not comply to the list of expected security attributes

Action:
Ensure the security attribute is one of the expected values i.e. user, group, application role, authenticated and anonymous roles

WCS-44305
An error occurred while upgrading portal role {0} due to {1}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The role may already have been upgraded.

Action:
Take action based on the underlying exception details.

WCS-44306
An error occurred while upgrading portal roles due to {0}

Category:
Security

Cause:
Review the underlying exception in the logs to determine the exact cause. The role may already have been upgraded.

Action:
Take action based on the underlying exception details.

WCS-47201
An unexpected error occurred in the Activity Stream sub-system.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47202
The publish activity failed because invalid arguments were passed to the method: activity ({0}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47203
The retrieve activities failed because invalid arguments were passed to the method: privateAndUpActorIds ({0}), sharedAndUpActorIds ({1}), publicActorIds ({2}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47205
Cannot establish connections. A connections exception was thrown.

Category:
Other

Cause:
A connections exception has been thrown.

Action:
Check the exception's details to see why it was thrown.

WCS-47206
A Service Framework exception was thrown.

Category:
Other

Cause:
A Service Framework exception has been thrown.

Action:
Check the exception's details to see why it was thrown.

WCS-47207
A Settings exception was thrown.

Category:
Other

Cause:
A Settings exception was thrown.

Action:
Check the exception's details to see why it was thrown.

WCS-47208
The retrieve activities failed because invalid arguments were passed to the method: applicationId ({0}), servivceId ({1}), activityType ({2}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47209
The retrieve activities failed because invalid arguments were passed to the method: applicationId ({0}), servivceId ({1}), activityType ({2}), sinceDate ({3}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47210
A database exception occurred in the Activity Stream Toplink module.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47211
A query exception occurred in the Activity Stream Toplink module.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47212
Create Actor failed because an invalid argument was passed to the method: guid ({0}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47213
Create Object failed because an invalid argument was passed to the method: guid ({0}), type ({1}), displayName ({2}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47214
Create Activity Element failed because an invalid argument was passed to the method: applicationID ({0}), scope ({1}), serviceID ({2}), activityType ({3}), actors ({4}), permission ({5}), activityTime ({6}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47215
Create Activity Type failed because an invalid argument was passed to the method: id ({0}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47216
Create Object Type failed because an invalid argument was passed to the method: id ({0}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47217
Create Activity Element failed because an invalid argument was passed to the method: applicationID ({0}), activityType ({1}), actors ({2}), permission ({3}), activityTime ({4}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47218
Publish activity {0} failed due to {1}.

Category:
Other

Cause:
An unexpected error during the publishing activity.

Action:
Contact Oracle Support Services.

WCS-47219
An error occurred due to {0}.

Category:
Other

Cause:
An exception occurred.

Action:
Contact Oracle Support Services.

WCS-47220
An unexpected error occurred resolving property "{0}":"{1}" for an Analytics event of type {2}

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47221
Unable to publish the Analytics event (of type {0}).

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47222
This operation is not supported.

Category:
Other

Cause:
This operation not supported.

Action:
Contact Oracle Support Services.

WCS-47223
Skipping profile information for user {0}

Category:
Other

Cause:

Action:

WCS-47224
For user {0}, the last accessed page couldn"t be found due to {1}

Category:
Other

Cause:

Action:

WCS-47225
Check for valid repository failed.

Category:
Other

Cause:
Either the database is down or the WebCenter repository is not installed.

Action:
Check the exception's details to why this error occurred.

WCS-47226
For user {0}, couldn''t retrieve the list of pages last accessed due to {1}

Category:
Other

Cause:

Action:

WCS-47227
For user {0}, couldn''t retrieve the last accessed page in {1} due to {2}

Category:
Other

Cause:

Action:

WCS-47228
For user {0}, couldn''t clean the last accessed page due to {1}

Category:
Other

Cause:

Action:

WCS-47229
The task flow instance was not specified.

Category:
Other

Cause:
The supplied taskflow instance ID was null or blank.

Action:
Specify a valid taskflow instance ID that is not null or blank.

WCS-47230
An activity exception was encountered during the bulk publish operation.

Category:
Other

Cause:
One or more activities threw an exception.

Action:
Check the individual activity exception.

WCS-47231
Create Cust Attr failed because an invalid argument was passed to the method: name ({0}), value ({1}), url ({2}).

Category:
Other

Cause:
One of the input arguments was invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47232
An unexpected error occurred while setting up the Comments service.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47233
An unexpected error occurred while retrieving comments.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47234
An unexpected error occurred while posting a comment.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47235
An unexpected error occurred while preparing a comments summary.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47236
An unexpected error occurred while preparing comments.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47237
Comment text cannot be empty.

Category:
Other

Cause:
The supplied text for the comment is null or blank.

Action:
Specify a non-empty text for the comment.

WCS-47238
An object was not specified.

Category:
Other

Cause:
The supplied object identifier is null.

Action:
Specify a non-null object identifier.

WCS-47239
An object ID is not present for the specified object.

Category:
Other

Cause:
The ID of the specified object is null.

Action:
Specify an object with a valid ID.

WCS-47240
A service ID is not present for the specified object.

Category:
Other

Cause:
The service ID for the specified object is null.

Action:
Specify an object with a valid service ID.

WCS-47241
An object type is not present for the specified object.

Category:
Other

Cause:
The object type for the specified object is null.

Action:
Specify an object with a valid object type.

WCS-47242
An unexpected error while expanding comments.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47243
An unexpected error occurred while collapsing comments.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47244
An unexpected error occurred while setting up the Likes service.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47245
An unexpected error occurred while retrieving Likes.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47246
An unexpected error occurred while retrieving Likes.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47247
An unexpected error occurred while posting a Like.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47248
A comment ID not specified.

Category:
Other

Cause:
The supplied comment ID was null or blank.

Action:
Specify a valid comment ID that is not null or blank.

WCS-47249
An unexpected error occurred while deleting a comment.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47250
An unexpected error occurred while initializing the scope.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47252
The follow object failed because an invalid arguments was passed to the method: actor ({0}), object ({1}), object service id ({2}).

Category:
Other

Cause:
One of the input arguments is invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47253
Can"t archive due to an invalid argument: date ({0}).

Category:
Other

Cause:
One of the input arguments is invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47254
An unexpected error occurred while archiving.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47255
Failed to register application management beans.

Category:
Other

Cause:
Application management beans(MBean) registration failed. Either there are issues with WebLogic or the application was not packaged properly.

Action:
Restart WebLogic or examine WebLogic log files for further details.

WCS-47256
Failed to unregister application management beans.

Category:
Other

Cause:
Application management beans(MBean) unregistration failed. Either the Mbeans were not registered or the Mbeans were already unregistered.

Action:
Examine the WebLogic log files for further details.

WCS-47257
An unexpected error occurred while deleting service data corresponding to the activity.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47258
The advanced query parameter contains invalid or unsupported constructs.

Category:
Other

Cause:
There are invalid or unsupported SQL constructs specified in the Advanced Query filter parameter.

Action:
Correct the Advanced Query filter parameter.

WCS-47259
An unexpected error occurred in setting up the JMS queue {0}.

Category:
Other

Cause:
The AQ JMS ConnectionFactory or Queue lookup failed.

Action:
Correct JMS Modules in Admin Console.

WCS-47260
An unexpected error occurred while send message to the JMS queue.

Category:
Other

Cause:
The JMS Queue found, but enqueue failed.

Action:
Examine the Weblogic log files for exception details.

WCS-47261
Fail to get Resource URI for published Activity.

Category:
Other

Cause:
The ResourceActionUtils.getUrl() failed for input Activity.

Action:
Examine the Weblogic log files for exception details.

WCS-47262
Fail to get Activity message for message key {0} in bundle {1}.

Category:
Other

Cause:
The getMessage() failed for input Activity.

Action:
Examine the Weblogic log files for exception details.

WCS-47263
Failed to unfollow objects due to {0}.

Category:
Other

Cause:
An unexpected error occurred during the unfollowing objects.

Action:
Contact Oracle Support Services.

WCS-47264
The unfollowed object failed because an invalid arguments was passed to the method: actor ({0}), object ({1}).

Category:
Other

Cause:
One of the input arguments is invalid.

Action:
Ensure that all arguments passed are valid.

WCS-47265
Failed to initialize context for asynchronous activity listeners processing.

Category:
Other

Cause:
Failed to initialize context for asynchronous activity listeners processing.

Action:
Contact Administrator.

WCS-47266
Failed to parse the activity definition file {0} due to {1}

Category:
Other

Cause:
Validate the activity-definition.xml file..

Action:
Examine the Weblogic log files for exception details.

WCS-47267
Failed to lookup connection for name {0}.

Category:
Other

Cause:
Invalid OSN connection name.

Action:
Contact Administrator.

WCS-47268
Could not load extension handler due to {0}.

Category:
Other

Cause:
Could not load extension handler.

Action:
Examine the WebCenter log files for exception details.

WCS-47269
Can not close transaction due to {0}.

Category:
Other

Cause:
Can not close transaction.

Action:
Examine the WebCenter log files for exception details.

WCS-47270
Can not close statement due to {0}.

Category:
Other

Cause:
Can not close statement.

Action:
Examine the WebCenter log files for exception details.

WCS-47271
Can not get result set due to {0}.

Category:
Other

Cause:
Can not get result set.

Action:
Examine the WebCenter log files for exception details.

WCS-47272
Can not rollback transaction due to {0}.

Category:
Other

Cause:
Can not rollback transaction.

Action:
Examine the WebCenter log files for exception details.

WCS-47273
Can not load XML actor detail data due to {0}.

Category:
Other

Cause:
Can not load XML actor detail data.

Action:
Examine the WebCenter log files for exception details.

WCS-47274
Can not insert new actor details due to {0}.

Category:
Other

Cause:
Can not insert new actor details.

Action:
Examine the WebCenter log files for exception details.

WCS-47275
Error occurs when processing activity {0} for activity listener{1} due to {2}.

Category:
Other

Cause:
Could not call activity listener's onsActivity method.

Action:
Examine the WebCenter log files for exception details.

WCS-47276
Failed while retrieving activity listeners due to {0}

Category:
Other

Cause:
Failed while retrieving activity listeners.

Action:
Examine the WebCenter log files for exception details.

WCS-47277
Failed to initialize due to {0}

Category:
Other

Cause:
Failed to initialize.

Action:
Examine the WebCenter log files for exception details.

WCS-47278
Cannot get service registry due to {0}.

Category:
Other

Cause:
Error to get service registry.

Action:
Examine the WebCenter log files for exception details.

WCS-47279
Error closing entity manager factory due to {0}

Category:
Other

Cause:
An unexpected exception occurred while closing the entity manager factory.

Action:
Review the exception thrown for more details.

WCS-47280
No default value found for key {0}.

Category:
Other

Cause:
No default value found for key {0}.

Action:
Ensure default value for key {0} is valid.

WCS-47281
Cannot get activity services list due to {0}.

Category:
Other

Cause:
Cannot get activity services list.

Action:
Examine the WebCenter log files for exception details.

WCS-47282
Resource bundle not found. bundle = {0}, key = {1} .

Category:
Other

Cause:
Resource bundle not found.

Action:
Examine the WebCenter log files for exception details.

WCS-47283
Key not found. bundle = {0}, key = {1} .

Category:
Other

Cause:
Key not found.

Action:
Examine the WebCenter log files for exception details.

WCS-47284
Service category {0} is invalid, title key not found, ignoring.

Category:
Other

Cause:
Service category is invalid, therefore title key not found.

Action:
Examine the WebCenter log files for exception details

WCS-47285
Unable to compare Service Settings due to {0}.

Category:
Other

Cause:
Unable to compare Service Settings.

Action:
Examine the WebCenter log files for exception details.

WCS-47286
Cannot parse to date due to {0}.

Category:
Other

Cause:
Cannot parse to date.

Action:
Examine the WebCenter log files for exception details.

WCS-47287
Cannot parse from date due to {0}.

Category:
Other

Cause:
Cannot parse from date.

Action:
Examine the WebCenter log files for exception details.

WCS-47288
Cannot set access control configurable due to {0}.

Category:
Other

Cause:
Cannot set access control configurable.

Action:
Examine the WebCenter log files for exception details.

WCS-47289
Cannot set configurable service category settings due to {0}.

Category:
Other

Cause:
Cannot set configurable service category settings.

Action:
Examine the WebCenter log files for exception details.

WCS-47290
Can not process activity {0} due to {1}.

Category:
Other

Cause:
>Can not process activity.

Action:
Examine the WebCenter log files for exception details.

WCS-47291
Failed to get profile guid {0} due to {1}.

Category:
Other

Cause:
Failed to get profile guid.

Action:
Examine the WebCenter log files for exception details.

WCS-47292
Failed to get profile id {0} due to {1}.

Category:
Other

Cause:
Failed to get profile guid.

Action:
Examine the WebCenter log files for exception details.

WCS-47293
Cannot summarize activities due to activity list is null.

Category:
Other

Cause:
Cannot summarize activities due mActivities is null.

Action:
Examine the WebCenter log files for more details.

WCS-47294
Cannot get object type display name due to {0}.

Category:
Other

Cause:
Cannot get object type display name.

Action:
Examine the WebCenter log files for more details.

WCS-47295
Could not publish activity even after retry due to {0}.

Category:
Other

Cause:
Could not publish activity even after retry.

Action:
Examine the WebCenter log files for more details.

WCS-47296
Error while retrieving activities due to {0}.

Category:
Other

Cause:
Error while retrieving activities.

Action:
Examine the WebCenter log files for more details.

WCS-47297
Error while processing personal criteria due to {0}.

Category:
Other

Cause:
Error while processing personal criteria.

Action:
Examine the WebCenter log files for more details.

WCS-47298
Error while processing portals criteria due to {0}.

Category:
Other

Cause:
Error while processing portals criteria.

Action:
Examine the WebCenter log files for more details.

WCS-47299
Error while processing service id criteria due to {0}.

Category:
Other

Cause:
Error while processing service id criteria .

Action:
Examine the WebCenter log files for more details.

WCS-47300
Error while processing activity type criteria due to {0}.

Category:
Other

Cause:
Error while processing activity type criteria.

Action:
Examine the WebCenter log files for more details.

WCS-47302
Error while processing enterprise id criteria due to {0}.

Category:
Other

Cause:
Error while processing enterprise id criteria.

Action:
Examine the WebCenter log files for more details.

WCS-47303
Error while processing date criteria due to {0}.

Category:
Other

Cause:
Error while processing date criteria.

Action:
Examine the WebCenter log files for more details.

WCS-47304
Skipping rendering activity {0} due to {1}.

Category:
Other

Cause:
Skipping rendering activity.

Action:
Examine the WebCenter log files for more details.

WCS-47305
Cannot get profile due to {0}.

Category:
Other

Cause:
Cannot get profile.

Action:
Examine the WebCenter log files for more details.

WCS-47306
Failed to get activity type icon url due to {0}.

Category:
Other

Cause:
Failed to get activity type icon url.

Action:
Examine the WebCenter log files for exception details.

WCS-47307
Failed to get activity type due to {0}.

Category:
Other

Cause:
Failed to get activity type.

Action:
Examine the WebCenter log files for exception details.

WCS-47308
Failed to get activity type category due to {0}.

Category:
Other

Cause:
Failed to get activity type category.

Action:
Examine the WebCenter log files for exception details.

WCS-47309
Failed to get inline preview due to {0}.

Category:
Other

Cause:
Failed to get inline preview.

Action:
Examine the WebCenter log files for exception details.

WCS-47310
Failed to get object type due to {0}.

Category:
Other

Cause:
Failed to get object type.

Action:
Examine the WebCenter log files for exception details.

WCS-47311
Client listener not supported {0}.

Category:
Other

Cause:
Client listener not supported.

Action:
Examine the WebCenter log files for exception details.

WCS-47312
Cannot convert user guid {0} to id due to {1}.

Category:
Other

Cause:
Cannot convert user guid to id.

Action:
Examine the WebCenter log files for exception details.

WCS-47313
Could not publish activity due to {0}.

Category:
Other

Cause:
Could not publish activity.

Action:
Examine the WebCenter log files for more details.

WCS-47314
Cannot get preference maps due to {0}.

Category:
Other

Cause:
Cannot get preference maps .

Action:
Examine the WebCenter log files for more details.

WCS-47315
Cannot obtain scope {0} due to {1}.

Category:
Other

Cause:
Cannot obtain scope.

Action:
Examine the WebCenter log files for more details.

WCS-47316
Failed to publish Activity. Activity Detail: {0}.

Category:
Other

Cause:
Could not publish activity.

Action:
Examine the WebCenter log files for more details.

WCS-47317
Failed to publish Activity. Actor Detail: {0}.

Category:
Other

Cause:
Could not publish activity.

Action:
Examine the WebCenter log files for more details.

WCS-47318
During creating of UI components, can not get the object type.

Category:
Other

Cause:
During creating of UI components, can not get the object type.

Action:
Examine the WebCenter log files for exception details.

WCS-47319
Failed to initialize activity stream settings due to {0}

Category:
Other

Cause:
Fail to initialize activity stream settings.

Action:
Examine the WebCenter log files for exception details.

WCS-47320
Cannot summarize activities due to {0}.

Category:
Other

Cause:
Cannot summarize activities.

Action:
Examine the WebCenter log files for more details.

WCS-47321
Cannot get service {0} due to {1}.

Category:
Other

Cause:
Error to get service.

Action:
Examine the WebCenter log files for exception details.

WCS-47322
An unexpected error occurred while saving settings.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47323
An unexpected error occurred while preparing the activity record.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47324
An unexpected error occurred while refreshing preference settings.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47325
An unexpected error occurred while removing the activity record.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47326
An unexpected error occurred while hiding the popup.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47327
An unexpected error occurred while preparing the activity view or components.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47328
An unexpected error occurred while fetching service IDs.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47329
An unexpected error occurred while initializing activity stream settings.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47330
An unexpected error occurred while saving or hiding preferences.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47331
An unexpected error occurred while fetching the portals.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47332
An unexpected error occurred while retrieving the activities.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47333
An unexpected error occurred while retrieving the summary activities.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47334
An unexpected error occurred while retrieving activities data.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47335
An unexpected error occurred while saving setup options.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47336
Input text 'No of activities to display per page' accepts positive value.

Category:
Other

Cause:
Wrong user input

Action:
Correct the invalid input and retry.

WCS-47695
Unexpected error saving settings

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47696
Fatal error initializing the settings management sub-system

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47697
Unexpected error retrieving settings

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47698
Unable to locate the settings document

Category:
Other

Cause:
Either the document path was incorrect or the document had got deleted.

Action:
Ensure that the document path is correct and that the document exists.

WCS-47699
Unable to determine current user

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47801
An unexpected error occurred in the Connections sub-system.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47802
User not specified

Category:
Other

Cause:
The supplied username was null or blank.

Action:
Specify a valid username that is not null or blank.

WCS-47803
Unexpected error retrieving connections for user "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47804
Unexpected error retrieving invitations for current user

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47805
User "{0}" not found

Category:
Other

Cause:
The system could not find any user with the specified username.

Action:
Specify a valid username.

WCS-47806
Unexpected error sending invitation to user "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47807
Invitation not found (the invitation may have been withdrawn, accepted, or declined already)

Category:
Other

Cause:
The system could not find any invitation with the specified ID.

Action:
Ensure that the specified invitation ID is valid.

WCS-47808
Invitation ID not specified

Category:
Other

Cause:
The supplied invitation ID was null or blank.

Action:
Specify a valid invitation ID that is not null or blank.

WCS-47809
Unexpected error accepting invitation with ID "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47810
Unexpected error declining invitation with ID "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47811
Unexpected error ignoring invitation with ID "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47812
Unexpected error removing connection with user "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47813
Unexpected error retrieving profile of user "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47814
Unexpected error retrieving the connection lists owned by user "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47815
Connection list not specified

Category:
Other

Cause:
The supplied connection list name was null or blank.

Action:
Specify a valid connection list name that is not null or blank.

WCS-47816
Connection list named "{0}" not found for user "{1}"

Category:
Other

Cause:
The system could not find any connection list with the specified name owned by the specified user.

Action:
Ensure that the username is correct and that the connection list name refers to a connection list owned by that user.

WCS-47817
Unexpected error getting Connection list "{0}" for user "{1}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47818
User does not have the privilege required to perform specified operation

Category:
Other

Cause:
Either the system policy or the target user's access control settings restrict the current user from performing this operation

Action:
Contact the Administrator to grant the required permission, or contact the target user to allow access

WCS-47819
Unexpected error creating a Connection list with name "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47820
Unexpected error adding users to Connection list with name "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47821
Unexpected error deleting Connection list with name "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47822
Unexpected error retrieving members of Connection list with name "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47823
Unexpected error retrieving invitations sent by current user

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47824
Unexpected error removing user "{0}" from one or more Connection lists

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47825
Unexpected error setting Connection list membership of user "{0}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47826
Unexpected error retrieving the Connection lists to which user "{0}" belongs

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47827
Unexpected error creating a connection between users "{0}" and "{1}"

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47829
Cannot invite oneself as a connection

Category:
Other

Cause:
You have specified yourself as the invitee.

Action:
Specify a username other than that of yourself.

WCS-47830
Cannot invite a user who has been invited already ({0})

Category:
Other

Cause:
The user you have specified has already been invited.

Action:
Wait for the invited user to act on your invitation.

WCS-47831
Cannot invite a user who has already invited you ({0})

Category:
Other

Cause:
The user you have specified has already invited you.

Action:
Accept the invitation you have received from the user.

WCS-47832
Cannot invite a user you are already connected with ({0})

Category:
Other

Cause:
You have specified one of your existing connections as the invitee.

Action:
Specify a username other than that of your existing connections.

WCS-47833
Unexpected error searching for users with filter pattern ({0})

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47834
Cannot create a connection between users "{0}" and "{1}" who already connected

Category:
Other

Cause:
The specified users are already connected with each other.

Action:
Specify users who are not yet connected.

WCS-47835
Unexpected error reading default configuration "{0}" or custom configuration

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47836
Unexpected error getting connections with preferences (userGuid = {0}, applicationId = {1}, scope = {2}, serviceId = {3}, settingKey = {4}, configurableSettingKey = {5})

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47837
Unexpected error getting connections lists with preferences (listNames = {0}, userGuid = {1}, applicationId = {2}, scope = {3}, serviceId = {4}, settingKey = {5}, configurableSettingKey = {6})

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-47838
Cannot create a Connection list with the same name as existing one ({0})

Category:
Other

Cause:
You already have a connection list with the specified name.

Action:
Specify a name other than that of your existing connection lists.

WCS-49001
Injectable Service provider did not set list service

Category:
Other

Cause:
Injectable Service provider could not find the list service.

Action:
Make sure List Service injectable provider is available in webapp.

WCS-49002
List id is null

Category:
Other

Cause:
List ID was not specified in request.

Action:
Make sure List ID is specified in request.

WCS-49003
Column id is null

Category:
Other

Cause:
Column ID was not specified in request.

Action:
Make sure Column ID is specified in request.

WCS-49004
Row id is null

Category:
Other

Cause:
Row ID was not specified in request.

Action:
Make sure Row ID is specified in request.

WCS-49005
No 'column' in the request body

Category:
Other

Cause:
Column data was not found in the request body.

Action:
Make sure Column data is specified in the request body.

WCS-49006
No 'list' in the request body

Category:
Other

Cause:
List data was not found in the request body.

Action:
Make sure List data is specified in the request body.

WCS-49007
No 'row' in the request body

Category:
Other

Cause:
Row data was not found in the request body.

Action:
Make sure Row data is specified in the request body.

WCS-49008
List could not be found for list id [{0}]

Category:
Other

Cause:
List ID was not found.

Action:
Make sure List ID exists.

WCS-49009
Column could not be found for column id [{0}]

Category:
Other

Cause:
Column ID was not found.

Action:
Make sure Column ID exists.

WCS-49010
Row could not be found for row id [{0}]

Category:
Other

Cause:
Row ID was not found.

Action:
Make sure Row ID exists.

WCS-49011
Unable to create list

Category:
Other

Cause:
List was not created.

Action:
See logs for more information.

WCS-49012
'id' should not be supplied with a POST -- use PUT if you want to update

Category:
Other

Cause:
'id' should not be supplied with a POST.

Action:
Use PUT if you want to update.

WCS-49013
Search parameter must follow [column:[operator:]]value;[column:[operator:]value] syntax

Category:
Other

Cause:
Search parameter syntax not understood.

Action:
Syntax must follow: [column:[operator:]]value;[column:[operator:]value]

WCS-49014
Comparator [{0}] is invalid

Category:
Other

Cause:
Invalid search comparator.

Action:
Use valid search comparator.

WCS-49015
MetaColumn [{0}] is a required field, and cannot be set to null

Category:
Other

Cause:
Missing required field.

Action:
Make sure required field is present.

WCS-49016
Invalid "row" data in the request body [{0}]

Category:
Other

Cause:
Invalid row data was found in the request body.

Action:
Make sure valid row data is specified in the request body.

WCS-49017
Portal name not found [{0}]

Category:
Other

Cause:
Portal name not found.

Action:
Please specify a valid portal name.

WCS-49018
Portal name not found for GUID [{0}]

Category:
Other

Cause:
Portal name GUID not found.

Action:
Please specify a valid portal name GUID.

WCS-49101
Injectable Service provider did not set forum service

Category:
Other

Cause:
Injectable Service provider could not find the forum service.

Action:
Make sure Forum Service injectable provider is available in webapp.

WCS-49102
Can't establish Forum Session

Category:
Other

Cause:
Injectable Service provider could not establish a Forum Session.

Action:
Make sure Jive Forum is configured and running and/or you have a valid user session established. Re-authenticating may help.

WCS-49103
Forum id not found [{0}]

Category:
Other

Cause:
Forum not found.

Action:
Please specify a valid forum.

WCS-49104
Portal name not found [{0}]

Category:
Other

Cause:
Portal name not found.

Action:
Please specify a valid portal name.

WCS-49105
All resources require a name.

Category:
Other

Cause:
Resource name required.

Action:
Please specify a resource name in the request body.

WCS-49106
Topic id not found [{0}]

Category:
Other

Cause:
Topic not found.

Action:
Please specify a valid topic.

WCS-49201
Injectable Service provider did not set Spaces service

Category:
Other

Cause:
Injectable Service provider could not find Space the service.

Action:
Make sure Space Service injectable provider is available in webapp.

WCS-49202
Portal id is null

Category:
Other

Cause:
Portal ID was not specified in request.

Action:
Make sure Portal ID is specified in request.

WCS-49203
No 'document' in the request body

Category:
Other

Cause:
Portal document data was not found in the request body.

Action:
Make sure Portal document is specified in the request body.

WCS-49204
Portal name not found [{0}]

Category:
Other

Cause:
Portal name not found.

Action:
Please specify a valid portal name.

WCS-49205
Members not found for portal [{0}]

Category:
Other

Cause:
No Members found.

Action:
Please specify a portal with members.

WCS-49206
Member [{0}] not found in portal [{1}]

Category:
Other

Cause:
Member not found.

Action:
Please specify a different member or portal name.

WCS-49207
Attributes not found in portal [{0}]

Category:
Other

Cause:
Attributes not found.

Action:
Please specify a different portal name.

WCS-49208
Attribute name [{0}] not found in portal [{1}]

Category:
Other

Cause:
Attribute name not found.

Action:
Please specify a different Attribute name or portal name.

WCS-49209
Portal params [{0}] and [{1}] result in exception

Category:
Other

Cause:
General exception.

Action:
Please specify a different set of parameters.

WCS-49210
Attempted operation resulted in security exception

Category:
Other

Cause:
Insufficient authorization.

Action:
Contact portal administrator.

WCS-49211
Retrieving Portal failed due to service unavailability

Category:
Other

Cause:
Service inaccessible.

Action:
Contact portal administrator.

WCS-49212
Failed to retrieve document repository info for portal.

Category:
Other

Cause:
Unknown document repository error.

Action:
Contact portal administrator.

WCS-49213
No Portal provided in body.

Category:
Other

Cause:
Portal was not provided in POST body of request.

Action:
Provide Portal in POST body of request.

WCS-49214
Portal template name not specified.

Category:
Other

Cause:
No portal template name was specified in POST body of request.

Action:
Please specify a portal template name.

WCS-49215
Portal name not specified.

Category:
Other

Cause:
No portal name was specified in POST body of request.

Action:
Please specify a portal name.

WCS-49216
Unable to create Portal.

Category:
Other

Cause:
Internal error creating Portal.

Action:
Contact portal administrator and/or see logs for additional errors.

WCS-49217
No Member provided in body.

Category:
Other

Cause:
Member was not provided in POST body of request.

Action:
Provide Member in POST body of request.

WCS-49218
Member name not specified.

Category:
Other

Cause:
No member name was specified in POST body of request.

Action:
Please specify a member name.

WCS-49219
Role name not specified.

Category:
Other

Cause:
No role name was specified in POST body of request.

Action:
Please specify a role name.

WCS-49220
Retrieving Portal Assets failed due to service unavailability

Category:
Other

Cause:
Service inaccessible.

Action:
Contact portal administrator.

WCS-49221
Injectable Service provider did not set Asset Lifecycle service

Category:
Other

Cause:
Injectable Service provider could not find Asset Lifecycle the service.

Action:
Make sure Asset Lifecycle Service injectable provider is available in webapp.

WCS-49222
Portal name specified for asset publishing not found : {0}

Category:
Other

Cause:
Portal name not found.

Action:
Specify a valid portal name.

WCS-49223
Archive for asset upload has not been provided

Category:
Other

Cause:
Asset archive for upload not provided.

Action:
Specify an asset archive for upload.

WCS-49224
Asset archive is invalid : {0}

Category:
Other

Cause:
Asset archive files or content is not packaged properly.

Action:
Include a valid asset archive. See associated message for more details.

WCS-49225
Portal template not found with the name not specified.

Category:
Other

Cause:
No portal template was found corresponding to the name specified in POST body of request.

Action:
Please specify an existing portal template name.

WCS-49251
REST API Injectable Service provider did not set message board service.

Category:
Other

Cause:
REST API Injectable Service provider did not set message board service.

Action:
Contact Oracle Support Services.

WCS-49252
No 'message' in the request body

Category:
Other

Cause:
Message data was not found in the request body.

Action:
Make sure Message data is specified in the request body.

WCS-49253
Message body not specified

Category:
Other

Cause:
No 'message' in the body when trying to create a new message.

Action:
Specify a valid message body that is not null or blank.

WCS-49254
'id' should not be supplied with a POST -- use PUT if you want to update

Category:
Other

Cause:
'id' should not be supplied with a POST.

Action:
Use PUT if you want to update.

WCS-49255
Error accessing profile for user with GUID {0}. Ignoring.

Category:
Other

Cause:
Error retrieving user profile.

Action:
Verify that the user GUID is correct.

WCS-49256
Permissions class called with wrong number of resource IDs. Expecting 2 or 3, but got {0}.

Category:
Other

Cause:

Action:

WCS-49257
Error accessing user or portal message board {0}.

Category:
Other

Cause:

Action:

WCS-49258
Error accessing message {0} from user or portal message board {1}.

Category:
Other

Cause:

Action:

WCS-49259
Error retrieving messages {0} to {1} from user or portal message board {2}.

Category:
Other

Cause:
Error retrieving message from user's message board.

Action:
Check startIndex and itemsPerPage.

WCS-49260
Error trying to delete message {0} from message board for user or portal {1}.

Category:
Other

Cause:

Action:

WCS-49261
Error trying to create message on message board for user or portal {0}.

Category:
Other

Cause:

Action:

WCS-49262
Invalid message board type. Got "{0}", expected "person" or "space".

Category:
Other

Cause:
Invalid message board type in URI.

Action:
Verify that the message board type is either 'person' or 'space'.

WCS-49263
Invalid message type. Got "{0}", expected "private", "public", "hidden", "private_hidden".

Category:
Other

Cause:
Invalid message type in URI.

Action:
Verify that the message type is either 'private', 'public', hidden' or 'private_hidden'.

WCS-49264
Message type "{0}" not supported with message board type "{1}".

Category:
Other

Cause:
Invalid message type in URI.

Action:
Verify that the message type is empty.

WCS-49265
Message type "{0}" not supported for users other than current user.

Category:
Other

Cause:
Invalid message type in URI.

Action:
Verify that the message type is empty.

WCS-49301
REST API Injectable Service provider did not set profile service.

Category:
Other

Cause:
REST API Injectable Service provider did not set profile service.

Action:
Contact Oracle Support Services.

WCS-49302
Cannot delete a member from a list that the current user does not own.

Category:
Other

Cause:
Cannot delete a member from a list that the current user does not own.

Action:
Make sure REST URL specifies the correct list and is accessing list for the current user.

WCS-49303
Retrieving list names is only supported for current user. Found GUID {0}.

Category:
Other

Cause:
Retrieving list names is only supported for current user.

Action:
Make sure REST URL specifies the current user GUID (or @me).

WCS-49304
Creating lists is only supported for the current user. Found GUID {0}.

Category:
Other

Cause:
Creating lists is only supported for current user.

Action:
Make sure REST URL specifies the current user GUID (or @me).

WCS-49305
No 'list' in the request body

Category:
Other

Cause:
List data was not found in the request body.

Action:
Make sure List data is specified in the request body.

WCS-49306
List name not specified

Category:
Other

Cause:
No 'name' in the body when trying to create a new list.

Action:
Specify a valid list name that is not null or blank.

WCS-49307
Creating connections is only supported for the current user. Found GUID {0}.

Category:
Other

Cause:
Creating connections is only supported for current user.

Action:
Make sure REST URL specifies the current user GUID (or @me).

WCS-49308
No 'member' in the request body

Category:
Other

Cause:
Member data was not found in the request body.

Action:
Make sure member data is specified in the request body.

WCS-49309
Connection GUID not specified

Category:
Other

Cause:
No 'guid' in the body when trying to create a new connection.

Action:
Specify a valid user GUID that is not null or blank.

WCS-49310
Only connection lists can be deleted, and only by the current user. Found GUID {0} and list ID {1}.

Category:
Other

Cause:
Only connection lists can be deleted, not the current user or the intrinsic connections list. They can only be deleted by the current user.

Action:
Make sure REST URL specifies the connection list ID, not @self or @connections, and is accessing the current user.

WCS-49311
Accessing status is only supported for @self id. Found selector {0}.

Category:
Other

Cause:
Accessing status is only supported for @self id.

Action:
Make sure REST URL specifies the @self selector.

WCS-49312
Updating status is only supported for the current user. Found GUID {0}.

Category:
Other

Cause:
Accessing status is only supported for the current user.

Action:
Make sure REST URL is accessing the current user.

WCS-49313
Error trying to access profile for user {0}.

Category:
Other

Cause:

Action:

WCS-49314
Error checking for people permissions. Wrong number of arguments. Expected 1-3, but found {0} for permission {1}. Ignoring.

Category:
Other

Cause:

Action:

WCS-49315
Error checking for people permissions. Could not parse type {0}. Expected: person, status, lists, list, member. Ignoring.

Category:
Other

Cause:

Action:

WCS-49316
Error trying to access connection lists for user {0}.

Category:
Other

Cause:

Action:

WCS-49317
Error accessing connection list {0}.

Category:
Other

Cause:
Error accessing connection list.

Action:
Verify that the list ID is correct.

WCS-49318
Error accessing connection relationship of user {0} to current user {1}.

Category:
Other

Cause:

Action:

WCS-49319
Error adding/deleting user {0} for list {1} of current user.

Category:
Other

Cause:
Error adding/deleting user in connection list of current user.

Action:
Verify that the list ID is correct and is not @CONNECTIONS (use invitations instead) and the user GUID is correct, and that the user is not already a member of the list when adding user.

WCS-49320
"Error using Resource Action Handler to get link to user {0}.

Category:
Other

Cause:

Action:

WCS-49321
Invalid user search query {0}. Unable to process search. Verify that the search query is of the form [loginid:equals:X] or [guid:equals:Y].

Category:
Other

Cause:
Invalid search query was passed into People REST API.

Action:
Verify that the search query is of the form [loginid:equals:X] or [guid:equals:Y].

WCS-49322
Error accessing connection list {0} for user {1}.

Category:
Other

Cause:
Error accessing connection list.

Action:
Verify that the list ID and GUID are correct.

WCS-49323
Invalid invitation search query {0}. Unable to process search. Verify that the search query is either [invitor:equals:@me] or [invitee:equals:@me].

Category:
Other

Cause:
Invalid search query was passed into People Invitations REST API.

Action:
Verify that the search query is either [invitor:equals:@me] or [invitee:equals:@me].

WCS-49324
No 'invitation' in the request body

Category:
Other

Cause:
Invitation data was not found in the request body when trying to create a new invitation.

Action:
Make sure Invitation data is specified in the request body.

WCS-49325
Invitation invitee GUID not specified

Category:
Other

Cause:
No 'invitee' item or 'guid' item in 'invitee' in the body when trying to create a new invitation.

Action:
Specify a valid invitee user GUID that is not null or blank.

WCS-49326
Error retrieving invitations for current user.

Category:
Other

Cause:

Action:

WCS-49327
Error inviting user {0} to be a connection of the current user

Category:
Other

Cause:
Error inviting user {0} to be a connection of the current user.

Action:
Verify the invitee user GUID is correct and is not null or blank.

WCS-49328
The invitation ID in the request body ({0}) did not match the ID in the query string ({1})

Category:
Other

Cause:
The invitation ID in the request body did not match the ID in the query string when trying to update invitation status.

Action:
Make sure the invitation ID specified in the request body matches the invitation ID in the query string.

WCS-49329
Error deleting invitation {0}

Category:
Other

Cause:
Error deleting invitation {0}.

Action:
Verify the invitation ID is correct, and that the current user has permissions to delete the invitation (i.e. created or received it).

WCS-49330
Unable to update invitation {0} with status {1}. Verify that the invitation id is valid, the current user has permission to update the invitation, and that the status is either "accepted" or "ignored".

Category:
Other

Cause:
Unable to update invitation status.

Action:
Verify that the invitation id is valid, the current user has permission to update the invitation, and that the status is either "accepted" or "ignored".

WCS-49331
Error inviting user {0} to be a connection of current user.

Category:
Other

Cause:
Error inviting user to be a connection of current user.

Action:
Verify that the user GUID is correct, and that the user has not already been invited by the current user.

WCS-49332
Error accessing relationship information for connections and invitations of current user.

Category:
Other

Cause:

Action:

WCS-49333
Unable to lookup email address {0}.

Category:
Other

Cause:
Unable to lookup email address.

Action:
Make sure the email address is correct, and the identity store is configure properly.

WCS-49334
Error creating connection list {0}. List already exists.

Category:
Other

Cause:
Error creating connection list. List already exists.

Action:
Choose a new name for the new connection list.

WCS-49351
REST API Injectable Service provider did not set activity service.

Category:
Other

Cause:
REST API Injectable Service provider did not set activity service.

Action:
Contact Oracle Support Services.

WCS-49352
No 'activity' in the request body

Category:
Other

Cause:
Activity data was not found in the request body.

Action:
Make sure Activity data is specified in the request body.

WCS-49353
'id' should not be supplied with a POST -- use PUT if you want to update

Category:
Other

Cause:
'id' should not be supplied with a POST.

Action:
Use PUT if you want to update.

WCS-49354
Creating activities requires the service ID and activity type to be present.

Category:
Other

Cause:
Creating activities requires the service ID and activity type.

Action:
Make sure the activity POST contains the service ID and activity type.

WCS-49355
Error accessing activity {0}.

Category:
Other

Cause:

Action:

WCS-49356
Error accessing activities for user {0}.

Category:
Other

Cause:

Action:

WCS-49357
Error accessing activities for Portal {0}.

Category:
Other

Cause:

Action:

WCS-49358
Error trying to access profile for user {0}.

Category:
Other

Cause:

Action:

WCS-49359
Unable to retrieve object type for parameter object {0} in activity {1}.

Category:
Other

Cause:

Action:

WCS-49360
Unable to retrieve object with index {0} for parameter object {1} in activity {2}, because there are only {3} objects available.

Category:
Other

Cause:

Action:

WCS-49361
Unable to parse key {0}, activity type {1}, service id {2}, activity id {3} for activity parameter. Should be of form "{actor[n]"} or "{object[n]"}.

Category:
Other

Cause:
Unable to parse key for activity parameter.

Action:
Make sure key starts with actor or object and the index is numeric.

WCS-49362
Unable to find Portal scope for {0}.

Category:
Other

Cause:
Unable to find Portal scope from specified value.

Action:
Make sure Portal value is correct.

WCS-49363
Unable to publish activity for service {0}.

Category:
Other

Cause:

Action:

WCS-49364
Error accessing comments for object {2} with service id {0} and type {1}.

Category:
Other

Cause:

Action:

WCS-49365
Error creating comment for object {2} with service id {0} and type {1}.

Category:
Other

Cause:

Action:

WCS-49366
Error deleting comment {0}.

Category:
Other

Cause:
Unable to delete comment.

Action:
Make sure current user has permission to delete this comment.

WCS-49367
Error accessing activity object with id {2} with service id {0} and type {1}.

Category:
Other

Cause:
Unable to access activity object.

Action:
Make sure the service id, object type, and object id are correct.

WCS-49368
Error accessing activity object details for object with id {2} with service id {0} and type {1}.

Category:
Other

Cause:
Unable to access activity object details.

Action:
Make sure the service id, object type, and object id are correct.

WCS-49369
Error accessing comments service.

Category:
Other

Cause:
Error accessing comments service.

Action:
Contact Oracle Support Services.

WCS-49370
REST API Injectable Service provider did not set comment service.

Category:
Other

Cause:
REST API Injectable Service provider did not set comment service.

Action:
Contact Oracle Support Services.

WCS-49371
No 'comment' in the request body

Category:
Other

Cause:
Comment data was not found in the request body.

Action:
Make sure comment data is specified in the request body.

WCS-49372
Creating comments requires the comment text to be present.

Category:
Other

Cause:
Creating comments requires the comment text.

Action:
Make sure the comment POST contains the comment text.

WCS-49373
Invalid data parameter "{0}" for activity. Must include "data", and may include "commentsSummary" and "likesSummary".

Category:
Other

Cause:
Invalid data parameter for activity.

Action:
Make sure the data parameter includes 'data'. 'commentsSummary' and 'likesSummary' are optional.

WCS-49374
Error accessing likes for object {2} with service id {0} and type {1}.

Category:
Other

Cause:

Action:

WCS-49375
Error creating like for object {2} with service id {0} and type {1}.

Category:
Other

Cause:

Action:

WCS-49376
Error deleting like {0}.

Category:
Other

Cause:
Unable to delete like.

Action:
Make sure current user has permission to delete this like.

WCS-49377
Error accessing likes service.

Category:
Other

Cause:
Error accessing likes service.

Action:
Contact Oracle Support Services.

WCS-49378
REST API Injectable Service provider did not set like service.

Category:
Other

Cause:
REST API Injectable Service provider did not set like service.

Action:
Contact Oracle Support Services.

WCS-49379
No 'like' in the request body

Category:
Other

Cause:
Like data was not found in the request body.

Action:
Make sure like data is specified in the request body.

WCS-49380
Activity ID is null

Category:
Other

Cause:
Activity ID cannot be null.

Action:
Use valid activity ID.

WCS-49382
Error accessing comments for activity {0}.

Category:
Other

Cause:

Action:

WCS-49383
Error creating comment for activity {0}.

Category:
Other

Cause:

Action:

WCS-49384
Error creating like for activity {0}.

Category:
Other

Cause:

Action:

WCS-49385
Error accessing likes for activity {0}.

Category:
Other

Cause:

Action:

WCS-49386
User has insufficient permission to access object {2} with service id {0} and type {1}.

Category:
Other

Cause:
Unable to access the object due to permission settings.

Action:
Make sure current user has permission to access this object.

WCS-49387
User has insufficient permission to access activity {0}.

Category:
Other

Cause:
Unable to access the object due to permission settings.

Action:
Make sure current user has permission to access this object.

WCS-49388
User has insufficient permission to access object {2} with service id {0} and type {1}.

Category:
Other

Cause:

Action:

WCS-49389
User has insufficient permission to access activity {0}.

Category:
Other

Cause:

Action:

WCS-49390
Unable to parse date {0}. Make sure date format is yyyy-MM-dd.

Category:
Other

Cause:
Date format is not correct.

Action:
Make sure date format is yyyy-MM-dd.

WCS-49401
REST API Injectable Service provider did not set feedback service.

Category:
Other

Cause:
REST API Injectable Service provider did not set feedback service.

Action:
Contact Oracle Support Services.

WCS-49402
No 'message' in the request body

Category:
Other

Cause:
Message data was not found in the request body.

Action:
Make sure Message data is specified in the request body.

WCS-49403
Message body not specified

Category:
Other

Cause:
No 'message' in the body when trying to create a new feedback item.

Action:
Specify a valid message body that is not null or blank.

WCS-49404
'id' should not be supplied with a POST -- use PUT if you want to update

Category:
Other

Cause:
'id' should not be supplied with a POST.

Action:
Use PUT if you want to update.

WCS-49405
Error retrieving display name from profile for user with GUID {0}. Ignoring.

Category:
Other

Cause:
Error retrieving user profile.

Action:
Verify that the user GUID is correct.

WCS-49406
Permissions class called with wrong number of resource IDs. Expecting 1 or 2, but got {0}.

Category:
Other

Cause:

Action:

WCS-49407
Error accessing feedback for user {0}.

Category:
Other

Cause:

Action:

WCS-49408
Error accessing feedback item from user {1}.

Category:
Other

Cause:

Action:

WCS-49409
Error retrieving received feedback items from {0} to {1} for user {2}.

Category:
Other

Cause:
Error retrieving received feedback for user.

Action:
Check startIndex and itemsPerPage.

WCS-49410
Error retrieving given feedback items from user {0} for items {1} to {2}.

Category:
Other

Cause:
Error retrieving feedback for user.

Action:
Check startIndex and itemsPerPage.

WCS-49411
Error trying to delete feedback {0}.

Category:
Other

Cause:

Action:

WCS-49412
Error trying to create feedback for user {0}.

Category:
Other

Cause:

Action:

WCS-49413
Unable to find link {0} for feedback item {1}..

Category:
Other

Cause:

Action:

WCS-49414
Error trying to get feedback for user. Either unknown GUID {0} or unknown selector {1}.

Category:
Other

Cause:
Either an unknown GUID was entered, expected @me or GUID or unknown selector was entered, expected @self, @all, or valid GUID. Selector can only be a valid GUID if the {guid} value entered is @me or the GUID of the current logged in user.

Action:
Double check the GUID or selector entered is valid.

WCS-49415
No 'receivedUser' in the request body

Category:
Other

Cause:
The received user data was not found in the request body.

Action:
Make sure the received user is specified in the request body.

WCS-49416
Invalid selector for creating feedback. Expected "@self", but found "{0}".

Category:
Other

Cause:
Feedback can only be POSTed to a URI of the form {guid}/@self.

Action:
Make sure the URI selector is @self.

WCS-49417
GUID specified in URI and GUID specified in POST body do not match. URI GUID was "{0}", POST body received user GUID was "{1}".

Category:
Other

Cause:
GUID in URI and GUID specified in POST body received user GUID must match.

Action:
Make sure the URI GUID and POST body received user GUID match.

WCS-49451
Error trying to access profile for user {0}.

Category:
Other

Cause:

Action:

WCS-49452
The current DB version does not support this REST API. Expected version 11.1.1.2.0 or greater.

Category:
Other

Cause:

Action:

WCS-49453
Unable to use Resource Action Handler to get link to object with type {0} from service {1} and ID {2}.

Category:
Other

Cause:

Action:

WCS-49454
The "{0}" parameter was not found in the query string, or was empty.

Category:
Other

Cause:
The query string was missing a required parameter.

Action:
Make sure the specified parameter is present in the query string and is not empty.

WCS-49455
The "{0}" date time parameter could not be parsed: "{1}"

Category:
Other

Cause:
The query string date time parameter was not formatted correctly.

Action:
Make sure the specified date time parameter is formatted according to the XSD spec: YYYY-MM-DD with optional time and timezone components hh:mm:ss, +HH:mm, -HH:mm, or Z. The time component may include milliseconds, but they will not be used.

WCS-49456
Unable to encode data for use in URI.

Category:
Other

Cause:

Action:

WCS-49457
Unable to decode data from URI: {0}.

Category:
Other

Cause:
Unable to decode data from URI.

Action:
Make sure the specified data is correctly URL encoded before being passed to the server.

WCS-49458
A query string parameter was set to the default value of "{0}", which is a default template parameter, not a valid value.

Category:
Other

Cause:
A query string parameter was set to a default template parameter value with a starting '{ and ending '}, which is not a valid value.

Action:
Make sure the query string parameter is either set to a valid value, or removed.

WCS-49459
Secure Enterprise Search is not configured.

Category:
Other

Cause:
SES Crawl is not enabled for this instance

Action:
Make sure crawl is enabled for Documents, Forums, and Portals sources

WCS-49460
This Secure Enterprise Search version is not supporting facets.

Category:
Other

Cause:
SES Version is not supporting faceted queries

Action:
Make sure to use the SES version that supports faceted serch

WCS-49461
No UriService is available for the REST resource {0}.

Category:
Other

Cause:
No UriService is available for the REST resource.

Action:
Make sure the REST resource is correctly configured and annotated.

WCS-49501
Injectable Service provider did not set search service

Category:
Other

Cause:
Injectable Service provider could not find the search service.

Action:
Make sure Search Service injectable provider is available in webapp.

WCS-49509
Column could not be found for column id [{0}]

Category:
Other

Cause:
Column ID was not found.

Action:
Make sure Column ID exists.

WCS-49513
Search parameter must follow [column:[operator:]]value;[column:[operator:]value] syntax

Category:
Other

Cause:
Search parameter syntax not understood.

Action:
Syntax must follow: [column:[operator:]]value;[column:[operator:]value]

WCS-49514
Search parameter must follow [column:[operator:]]value;[column:[operator:]value] syntax

Category:
Other

Cause:
Search parameter syntax not understood.

Action:
Syntax must follow: [column:[operator:]]value;[column:[operator:]value]

WCS-49515
Comparator [{0}] is invalid

Category:
Other

Cause:
Invalid search comparator.

Action:
Use valid search comparator.

WCS-49516
Invalid argument: [{0}]

Category:
Other

Cause:
Invalid search argument.

Action:
Use valid search argument.

WCS-49517
Internal Search Error: [{0}]

Category:
Other

Cause:
Internal search error.

Action:
Please see error on server console.

WCS-49551
REST API Injectable Service provider did not set event service.

Category:
Other

Cause:
REST API Injectable Service provider did not set event service.

Action:
Contact Oracle Support Services.

WCS-49552
Unable to find Portal scope for {0}.

Category:
Other

Cause:
Unable to find Portal scope from specified value.

Action:
Make sure Portal value is correct.

WCS-49553
Unable to access calendar for scope {0}.

Category:
Other

Cause:
Unable to access requested calendar.

Action:
Make sure the scope value is a valid Portal GUID.

WCS-49554
Unable to access event {0} in Portal scope {1}.

Category:
Other

Cause:
Unable to access Portal event.

Action:
Make sure Portal and event ID values are correct.

WCS-49555
Unable to create event in Portal scope {1}.

Category:
Other

Cause:
Unable to create Portal event.

Action:
Make sure the Portal ID is correct and the current user has permission to create an event in that Portal.

WCS-49556
Unable to update event {0} in Portal scope {1}.

Category:
Other

Cause:
Unable to update Portal event.

Action:
Make sure Portal and event ID values are correct.

WCS-49557
Unable to delete event {0} in Portal scope {1}.

Category:
Other

Cause:
Unable to delete Portal event.

Action:
Make sure Portal and event ID values are correct.

WCS-49558
No 'event' in the request body.

Category:
Other

Cause:
Event data was not found in the request body.

Action:
Make sure Event data is specified in the request body.

WCS-49559
Event POST or PUT request bodies cannot contain the ID, author, created date, modifier, modified date, or duration.

Category:
Other

Cause:
Event POST or PUT request bodies cannot contain the ID, author, created date, modifier, modified date, or duration.

Action:
Make sure Event data does not contain the ID, author, created date, modifier, modified date, or duration in the request body.

WCS-49560
The event object was missing required data. Events are required to have summary, startTime, and endTime data.

Category:
Other

Cause:
The event object was missing required data.

Action:
Make sure Event summary, startTime, and endTime data are specified in the event object.

WCS-49561
Invalid portal GUID {0}.

Category:
Other

Cause:
This GUID does not refer to a valid portal.

Action:
Make sure the portal GUID is not null or empty, and refers to a valid portal. Home Portal cannot be used for portal events.

WCS-49562
Invalid time sequence: startTime {0} must be before endTime {1}..

Category:
Other

Cause:
The startTime must be before the endTime.

Action:
Make sure the startTime is before the endTime.

WCS-49563
Unable to access event categories for Portal scope {0}.

Category:
Other

Cause:
Unable to access Portal event categories.

Action:
Make sure Portal guid is correct.

WCS-49564
Unable to create event category {0} in Portal scope {1}.

Category:
Other

Cause:
Unable to create Portal event category.

Action:
Make sure the Portal ID is correct and the current user has permission to create an event category in that Portal.

WCS-49565
Unable to delete event category {0} in Portal scope {1}.

Category:
Other

Cause:
Unable to delete Portal event category.

Action:
Make sure Portal and event category name values are correct.

WCS-49601
Injectable Service provider did not set tagging service

Category:
Other

Cause:
Injectable Service provider could not find the tagging service.

Action:
Make sure Tagging Service injectable provider is available in webapp.

WCS-49613
Required query Parameter "{0}" was not found.

Category:
Other

Cause:
Query parameter "{0}" omitted or null.

Action:
Query parameter "{0}" required. Please try again with a non-null value for this parameter

WCS-49614
{1} Body must include "{0}" as a field. Could not complete POST Request.

Category:
Other

Cause:
{1} Body must include "{0}" as a field.

Action:
Provide a complete {1} Object as the body for this request

WCS-49615
Tag {0} could not be deleted.

Category:
Other

Cause:
There was an error while deleting this item

Action:
Please check if item exists and if you have the appropriate permissions to delete this item.

WCS-49616
Item with service Id: {0} and resource id: {1} could not be deleted.

Category:
Other

Cause:
There was an error while deleting this item

Action:
Please check if item exists and if you have the appropriate permissions to delete this item.

WCS-49617
Item with service id: {0} and resource id: {1} is already tagged by you

Category:
Other

Cause:
There was an error while tagging this item

Action:
Please check if item exists and if you have the appropriate permissions to tag this item.

WCS-49618
Item with service id: {0} and resource id: {1} was not found

Category:
Other

Cause:
There was an error while finding this item

Action:
Please check if item exists and if you have the appropriate permissions to tag this item.

WCS-49619
Tag {0} could not be found.

Category:
Other

Cause:
There was an error while finding this tag

Action:
Please check if item exists and if you have the appropriate permissions to tag this item.

WCS-49620
Required query Parameter "{0}" was not valid.

Category:
Other

Cause:
Query parameter "{0}" not valid.

Action:
Query parameter "{0}" required. Please try again with a valid value for this parameter

WCS-49651
REST API Injectable Service provider did not set links service.

Category:
Other

Cause:
REST API Injectable Service provider did not set links service.

Action:
Contact Oracle Support Services.

WCS-49652
No 'source' in the request body

Category:
Other

Cause:
Links source object was not found in the request body.

Action:
Make sure source object is specified in the request body.

WCS-49653
No 'target' in the request body

Category:
Other

Cause:
Links target object was not found in the request body.

Action:
Make sure target object is specified in the request body.

WCS-49654
Error trying to create links.

Category:
Other

Cause:
Error trying to create links

Action:
Make sure webcenter repository is available.

WCS-49655
No 'link' in the request body

Category:
Other

Cause:
Link data was not found in the request body.

Action:
Make sure Link data is specified in the request body.

WCS-49656
Unable to create link

Category:
Other

Cause:
Link was not created.

Action:
See logs for more information.

WCS-49657
Source "serviceid" or "resourceid" not specified

Category:
Other

Cause:
No source "serviceid" or "resourceid" when trying to create a link.

Action:
Specify valid "serviceid" and "resourceid" that are not null or blank.

WCS-49658
Target "serviceid" or "resourceid" not specified

Category:
Other

Cause:
No target "serviceid" or "resourceid" when trying to create a link.

Action:
Specify valid "serviceid" and "resourceid" that are not null or blank.

WCS-49659
Attempted operation resulted in security exception

Category:
Other

Cause:
Insufficient authorization.

Action:
Contact portal administrator.

WCS-49701
Injectable Service provider did not set recommendation service

Category:
Other

Cause:
Injectable Service provider could not find the recommendation service.

Action:
Make sure the Activity Graph Service injectable provider is available in webapp.

WCS-49702
A database exception occured when connecting to the recommendation service

Category:
Other

Cause:
A database exception occured when connecting to the recommendation service

Action:
Make sure the Activities data source is correctly configured and that the database server is working.

WCS-49703
The Activity Graph engines have not been run yet; there is no data to query. Please contact your administrator to configure and run the Activity Graph engines.

Category:
Other

Cause:
The Activity Graph engines have not been run yet and there is no data to query.

Action:
Please contact your administrator to configure and run the Activity Graph engines.

WCS-49704
An exception occured when connecting to the recommendation service

Category:
Other

Cause:
An exception occured when connecting to the recommendation service

Action:
Make sure the Activity Graph server is correctly configured and is working.

WCS-49705
The item class urn and object urns in the request body ({0}, {1}) did not match the values in the path ({2}, {3})

Category:
Other

Cause:
The item class urn and object urns in the request body did not match the values in the path when trying to update item status.

Action:
Make sure the item class urn and object urn specified in the request body matches the values in the uri path.

WCS-49706
Unable to update item {0}, {1} with status {2}. Verify that the item''s class URN and object URN are valid, that the current user has permission to update the item, and that the status is either "interested" or "not interested".

Category:
Other

Cause:
Unable to update the item's status.

Action:
Verify that the item's class URN and object URN are valid, that the current user has permission to update the item, and that the status is either "interested" or "not interested".

WCS-49707
Unable to update item. Verify that the item's class URN and object URN are valid.

Category:
Other

Cause:
The item's class URN and object URN must be specified

Action:
Verify that the item's class URN and object URN are valid and specified

WCS-49708
Unable to query for common items. Verify that the required parameters are valid and specified.

Category:
Other

Cause:
One or more mandatory query parameters have not been specified.

Action:
Verify that the required parameters are valid and specified.

WCS-49709
Unable to query for recommendations. Verify that the required parameters are valid and specified. You need to provide a recipe, an objectURN and either a classURN or serviceId parameters.

Category:
Other

Cause:
One or more mandatory query parameters have not been specified.

Action:
Verify that the required parameters are valid and specified. You need to provide a recipe, an objectURN and either a classURN or serviceId parameters.

WCS-49710
One of the query arguments is invalid. Verify that all arguments are correct, and that recipe and similarity URNs match the specified object types.

Category:
Other

Cause:
One or more query parameters is invalid.

Action:
Verify that all arguments are correct, and that recipe and similarity URNs match the specified object types.

WCS-49711
The following recipe is invalid: {0}. Verify that all similarity URNs are correct, that each URN has a positive weight, and that the recipe is formatted like this: item-edit:100;item-tag:10.

Category:
Other

Cause:
The recipe is invalid.

Action:
Verify that all similarity URNs are correct, that each URN has a positive weight, and that the recipe is formatted like this: item-edit:100;item-tag:10.

WCS-49712
The Activity Graph service is not present in this installation. It has either not been installed or not been configured correctly. Please contact your administrator to install and configure the Activity Graph service.

Category:
Other

Cause:
The Activity Graph service is not present in this installation. It has either not been installed or not been configured correctly.

Action:
Please contact your administrator to install and configure the Activity Graph service.

WCS-49713
Unable to query for top items. Verify that the required parameters are valid and specified.

Category:
Other

Cause:
One or more mandatory query parameters have not been specified.

Action:
Verify that the required parameters are valid and specified.

WCS-49714
Unable to query for autocompletions because the query string or index URNs are empty or missing. Verify that the required query string and index URN arguments are present and not empty.

Category:
Other

Cause:
The autocomplete query string or index URNs are missing.

Action:
Verify that the autocomplete query string and index URN arguments are present and not empty.

WCS-49715
The Activity Graph autocomplete engine has not been run yet; there is no data to query. Please contact your administrator to configure and run the Activity Graph engines.

Category:
Other

Cause:
The Activity Graph autocomplete engine has not been run yet and there is no data to query.

Action:
Please contact your administrator to configure and run the Activity Graph engines.

WCS-49716
An exception occured when connecting to the autocomplete service

Category:
Other

Cause:
An exception occured when connecting to the autocomplete service

Action:
Make sure the Activity Graph server is correctly configured and is working.

WCS-49801
Invalid ID

Category:
Other

Cause:
ID provided in the URL or query parameters is incorrect.

Action:
Make sure provided IDs in path or parameters are correct.

WCS-49802
Portal Not Found

Category:
Other

Cause:
Portal does not exist.

Action:
Make sure you specify the correct portal ID is provided and that this portal has not been deleted.

WCS-49803
Could not create object.

Category:
Other

Cause:
Could not create object based on provided PropertyBean.

Action:
Make sure valid paramters were passed for object creation.

WCS-49804
Invalid Query or OrderBy Parameter {0}.

Category:
Other

Cause:
Query or OrderBy param provided in the URL is incorrect.

Action:
Verify that the query name and query parameters you specified are correct. For more information, refer to the PortalQuery API documentation.

WCS-49805
Portal specified with short ID {0} not found.

Category:
Other

Cause:
Portal not found.

Action:
Specify a valid portal short id.

WCS-49806
Portal archive for import has not been provided. Specify the portal archive against the control name {0}.

Category:
Other

Cause:
Portal archive for import not provided.

Action:
Specify a portal archive for import archive against the control name fileName.

WCS-49807
Failed to create temporary directory within 5 attempts.

Category:
Other

Cause:
Failed to create temporary directory.

Action:
Make sure you have read and write permissions on the temporary locations on the server.

WCS-49808
Asset specified for download operation with short ID {0} not found.

Category:
Other

Cause:
Asset not found.

Action:
Specify a valid asset short id.

WCS-49809
Asset specified for download operation with short ID {0} does not belong to the portal {1}.

Category:
Other

Cause:
Asset specified for download operation does not belong to the specified portal.

Action:
Specify a valid asset short id which belongs to the specified portal.

WCS-49810
Asset archive for upload has not been provided. Specify the asset archive against the control name {0}.

Category:
Other

Cause:
Asset archive for upload not provided.

Action:
Specify an asset archive for upload archive against the control name fileName.

WCS-49811
Invalid limit ({0}) or offset ({1}) value for REST query.

Category:
Other

Cause:
Invalid limit or offset value for REST query.

Action:
Make sure the limit is greater than zero and the offset is greater than or equal to zero.

WCS-49812
The portal archive specified is invalid. Specify a valid archive that exists on the file system, and try again.

Category:
Other

Cause:
The portal archive specified is invalid.

Action:
Specify a valid portal archive for upload against the fileName attribute.

WCS-49813
The asset archive specified is invalid. Specify a valid archive that exists on the file system, and try again.

Category:
Other

Cause:
The asset archive specified is invalid.

Action:
Specify a valid asset archive for upload against the fileName attribute.

WCS-49814
Unable to clean up after creation failed for portal template {0}.

Category:
Other

Cause:
Portal template creation has failed and cleanup has failed.

Action:
Check the underlying exception.

WCS-49815
Unable to clean up after creation failed.

Category:
Other

Cause:
Creation has failed and cleanup has failed.

Action:
Check the underlying exception.

WCS-49816
Seeded asset modification is not allowed.

Category:
Other

Cause:
Seeded asset modification is not allowed.

Action:
Seeded asset modification is not allowed.

WCS-49817
Failed to add custom attribute to spaces.xml file due to {0}.

Category:
Other

Cause:
Failed to add custom attribute to spaces.xml file.

Action
Take action based on the underlying exception.

WCS-49818
Attribute [{0}] not found in portal [{1}]

Category:
Other

Cause:
Attribute name not found.

Action
Please specify a different Attribute name or portal name.

WCS-49819
Duplicate Attribute [{0}] in portal [{1}]

Category:
Other

Cause:
Duplicate attribute can not be added.

Action
Please specify a different Attribute name or portal name.

WCS-49820
Attributes not found in portal [{0}]

Category:
Other

Cause:
Attributes not found.

Action
Please specify a different portal name.

WCS-49821
Attribute name/value can not be null/empty

Category:
Other

Cause:
null/empty value is not accepted

Action
Please specify the attribute name/value.

WCS-50001
An unexpected error occurred in the notification sub-system.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-50002
Error in Notification Button tag usage - component {0} has attribute {1} whose value is {2}.

Category:
Other

Cause:
The attribute mentioned in the error cannot be null, but no value was found for this attribute.

Action:
Correct your tag usage.

WCS-50003
Component {0} does not support client listeners.

Category:
Other

Cause:
Tried to add a client listener to a component that does not support client listeners.

Action:
Contact Oracle Support Services.

WCS-50004
Mandatory parameter {0} not provided in parameters

Category:
Other

Cause:
The caller did not provide the required parameter to generate notification

Action:
Contact your system administrator

WCS-50005
Notification template {0} not found

Category:
Other

Cause:
The service failed to read the notification template. The template is not available

Action:
Contact your system administrator

WCS-50006
Could not create notification contents based on default template {0}

Category:
Other

Cause:
The service failed to process the default notification template.

Action:
Contact your system administrator

WCS-50007
Invalid child element {0} found for parent {1}

Category:
Other

Cause:
The template contains invalid child elements.

Action:
Contact your system administrator

WCS-50008
End tag {0} not found in CDATA section corresponding to the tag at index {2}

Category:
Other

Cause:
The CDATA section of the template contains a notification tag without corresponding end tag.

Action:
Contact your system administrator

WCS-50009
Value for the token {0} not found in parameters

Category:
Other

Cause:
The value for the token is not provided in the list of parameter values

Action:
Contact your system administrator

WCS-50010
Message key {0} not defined in resource bundle of service {1}

Category:
Other

Cause:
The message key used in the template does not exist in the service resource bundle

Action:
Contact your system administrator

WCS-50011
Error occurred in parsing message {0} in resource bundle of service {1}

Category:
Other

Cause:
The message has invalid syntax

Action:
Contact your system administrator

WCS-50012
An unexpected error occurred in the notification sub-system.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact your system administrator.

WCS-50013
Failed to add subscription.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-50014
Failed to remove subscription.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-50015
Failed to query subscription.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-50016
Failed to update subscription.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-50017
Failed to save subscription.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-50018
Failed to remove subscription.

Category:
Other

Cause:
Subscription does not exist

Action:
Resubmit the request with correct parameters

WCS-50019
Subscription cannot be added.

Category:
Other

Cause:
Subscription content is empty

Action:
Provide a non empty description

WCS-50020
Error occurred in initializing the notification sender

Category:
Other

Cause:
Failed initialize notification sender

Action:
Contact Administrator

WCS-50021
Error occurred in sending notification

Category:
Other

Cause:
Failed to send notification

Action:
Contact Administrator

WCS-50022
Fail to get UMS instance url.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact your system administrator.

WCS-50023
Error occurred in saving user preference settings

Category:
Other

Cause:
Failed to save user preference settings

Action:
Contact Administrator

WCS-50024
The settings document is invalid

Category:
Other

Cause:
Contents of the settings document are invalid

Action:
Verify and correct the settings document

WCS-50025
Fail to get user preference settings for the service {0}

Category:
Other

Cause:
Fail to get user preference settings for the service

Action:
Verify and correct the service

WCS-50026
Service Framework Exception is thrown.

Category:
Other

Cause:
Service Framework exception thrown.

Action:
Check the exception's detail to see the reason why the exception is thrown.

WCS-50027
Notification sender is not configured

Category:
Other

Cause:
Notification sender is not configured

Action:
Contact Administrator

WCS-50028
Error in parsing notification configuration

Category:
Other

Cause:
Error in parsing notification configuration

Action:
Contact Administrator

WCS-50029
Error processing activity for notifications

Category:
Other

Cause:
Error in processing activity for notification

Action:
Contact Administrator

WCS-50030
Failed to initialize context for asynchronous processingError processing

Category:
Other

Cause:
Failed to initialize context for asynchronous processingError processing

Action:
Contact Administrator

WCS-50031
Unexpected error occurred, please retry the unsubscribe operation

Category:
Other

Cause:
An internal error occurred

Action:
Retry the unsubscribe operation. Contact Oracle Support Services if the issue persists.

WCS-50032
Can not find scope for the given name

Category:
Other

Cause:
The given scope name is invalid

Action:
Verify and correct the scope name

WCS-50033
An unexpected error occurred while retrieving configuration document.

Category:
Other

Cause:
Failed to get configuration document.

Action:
Contact Administrator.

WCS-50034
An unexpected error occurred while retrieving service name for service id {0}.

Category:
Other

Cause:
Failed to get service name.

Action:
Contact Administrator.

WCS-50035
An unexpected error occurred while retrieving subscription object type.

Category:
Other

Cause:
Failed to get subscription object type.

Action:
Contact Administrator.

WCS-50036
An unexpected error occurred while sending UMS notification message.

Category:
Other

Cause:
Failed to send UMS notification message.

Action:
Contact Administrator.

WCS-52002
error obtaining content repository connection

Category:
Other

Cause:
A JNDI naming exception occurred while attempting to obtain the content repository connection.

Action:
Verify that connections.xml contains a valid entry for the content repository connection.

WCS-52003
error obtaining blog folder for the page

Category:
Other

Cause:
The blog folder for the page cannot be found or created.

Action:
Check the server logs for details on this exception.

WCS-52004
After fail-over, failed to get the item {0} from the repository.

Category:
Other

Cause:

Action:

WCS-52005
error obtaining blog entry for the page

Category:
Other

Cause:
The blog entry for the page cannot be found.

Action:
Check the server logs for details on this exception.

WCS-62001
Unexpected error occurred while saving translations for {0},{1}.

Category:
Other

Cause:
Unexpected error getting translations.

Action:
Contact Oracle support services.

WCS-62002
Unexpected error loading translations into WebCenter Portal.

Category:
Other

Cause:
Unexpected error loading translations.

Action:
Contact Oracle support services.

WCS-62003
The MDS Root location for loading translations cannot be null.

Category:
Other

Cause:
Null MDS root provided for loading translations.

Action:
Please specify a valid MDS root location.

WCS-63001
An unexpected error occurred.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-63002
An object of type {0} with this id ({1}) already exits.

Category:
Other

Cause:
An attempt was made to create an object with an id that is already in use.

Action:
Specify a unique id.

WCS-63003
The name ({0}) is not valid.

Category:
Other

Cause:
The specified name is not valid.

Action:
Specify a valid name.

WCS-63004
Object has been changed by another user.

Category:
Other

Cause:
The object has been changed by another user.

Action:
Reload the object and try the operation again.

WCS-63005
An Object of type {0} with id={1} could not be found.

Category:
Other

Cause:
The specified object could not be found. This may be due to the object being deleted by another user.

Action:
Specify a valid id.

WCS-63006
Object ({0}) is immutable.

Category:
Other

Cause:
An attempt to change this object was made, but this object is currently immutable.

Action:
Retrieve mutable object to make changes.

WCS-63007
{0} is not a valid reference name to MDS.

Category:
Other

Cause:
The name is not a valid MDS reference name.

Action:
Contact Oracle Support Services.

WCS-63008
The MDS session does not support updates.

Category:
Other

Cause:
MDS was not configured correctly to support updates.

Action:
Configure the MDS store to support updates.

WCS-63009
An IO error occurred when accessing metadata.

Category:
Other

Cause:
An IO error occurred in MDS.

Action:
See the log for more details on the specific IO error to correct the problem.

WCS-63010
The object is not valid.

Category:
Other

Cause:
The metadata for the object does not pass validation.

Action:
Contact Oracle Support Services.

WCS-63011
Failed to construct attribute set for list [{0}].

Category:
Other

Cause:
Failed to construct attribute set for list.

Action:
Contact Oracle Support Services.

WCS-63012
Failed to add data flavor to ListTransferable. List=[{0}] DataFlavor=[{1}]

Category:
Other

Cause:
Failed to add data flavor to ListTransferable.

Action:
Contact Oracle Support Services.

WCS-63013
The query attribute predicate {0}{1}{2} was ignored because the column does not exist or the comparator is not supported.

Category:
Other

Cause:

Action:

WCS-63014
An error occurred when deleting metadata.

Category:
Other

Cause:
An error occurred in MDS while deleting metadata.

Action:
See the log for more details on the specific error to correct the problem.

WCS-63015
A column with the name ({0}) already exists.

Category:
Other

Cause:
A column was created or renamed with the name of an existing column in the list.

Action:
Specify a unique column name within the list.

WCS-63016
A list with the name ({0}) already exists.

Category:
Other

Cause:
A list was created or renamed with the name of an existing list.

Action:
Specify a unique list name.

WCS-63017
The maximum number of columns for this list has been exceeded.

Category:
Other

Cause:
A list was created or modified with more than 30 columns.

Action:
Do not add more than 30 columns to a list.

WCS-63019
The Lists service is not provisioned for scope {0}.

Category:
Other

Cause:
The Lists service is not provisioned for the specified scope.

Action:
Provision the Lists service for the specified scope.

WCS-63020
The value is the wrong data type. The data type expected is {0}.

Category:
Other

Cause:
The value is the wrong data type.

Action:
Use the value with the correct data type.

WCS-63021
The WebCenter repository is not available.

Category:
Other

Cause:
An error occurred accessing the repository.

Action:
Contact your system administrator. Check the log for more details.

WCS-63022
An error occurred accessing the WebCenter metadata repository.

Category:
Other

Cause:
An error occurred accessing the repository.

Action:
Contact your system administrator. Check the log for more details.

WCS-63023
List column values were converted or deleted based on list column changes during import: scope={0}, list={1}, column={2}.

Category:
Other

Cause:

Action:

WCS-64001
JAXRS framework encryption service threw exception with message {0}.

Category:
Other

Cause:
JAXRS framework encryption service not initialized correctly.

Action:
Ensure JAXRS framework encryption service is initialized.

WCS-64002
JAXRS framework encryption service set up required. Key generator algorithm not set up in credential store framework.

Category:
Other

Cause:
Key generator algorithm not set up in credential store framework.

Action:
Set up key generator algorithm in credential store framework.

WCS-64003
JAXRS framework encryption service set up required. Cipher transformation not set up in credential store framework.

Category:
Other

Cause:
Cipher transformation not set up in credential store framework.

Action:
Set up cipher transformation in credential store framework.

WCS-64005
The ResourceType element named \"{0}\" is missing its \"{1}\" element.

Category:
Other

Cause:
The specified element is required by ResourceType element and cannot be empty.

Action:
Correct the ResourceType by setting the specified element to a non-empty value.

WCS-64006
ResourceType maps require the key element to be of type String.

Category:
Other

Cause:
The ResourceType map key should be of type String.

Action:
Correct the ResourceType by setting the specified map key to a String.

WCS-64007
The ResourceType element \"resourceTypeUrn\" requires a urn value.

Category:
Other

Cause:
The specified element value is required by ResourceType.

Action:
Correct the ResourceType by setting the specified element to a non-empty value.

WCS-64008
The ResourceType element named \"{0}\" must match the end of the resourceType urn name, \"{1}\".

Category:
Other

Cause:
The end of the resourceType urn name must match the element's name.

Action:
Correct the ResourceType by setting the specified element's name to the end of the resourceType urn string.

WCS-64010
The resource config provider cannot be instantiated.

Category:
Other

Cause:
The resource config provider for Jersey servlet is not configured properly.

Action:
Check web.xml to make sure the resource config provider is configured correctly.

WCS-64011
The TokenManager is not initialized.

Category:
Other

Cause:
The Token Manager is not configured correctly and cannot be initialized.

Action:
Check web.xml to make sure the Token Manager is configured correctly.

WCS-64012
Failed to set capabilities for REST resource type {0} due to exception {1}.

Category:
Other

Cause:
Failed to set capabilities for REST resource.

Action:
Make sure REST resource is annotated correctly.

WCS-64013
Null injectee in REST injection resolver class {0}.

Category:
Other

Cause:
Null injectee in REST injection resolver class.

Action:
Make sure REST servlet and resources are configured correctly.

WCS-64014
Missing WebCenter resource registration class.

Category:
Other

Cause:
The WebCenter resource registration class is missing.

Action:
Make sure a WebCenter resource registration class is implemented and registered in the web.xml file and mapped to the oracle.jaxrs.config.registration context parameter.

WCS-64015
The WebCenter resoruce registration class {0} is incorrectly implemented.

Category:
Other

Cause:
The WebCenter resource registration class does not implement the WebCenterResourceRegistration interface.

Action:
Make sure the WebCenter resource registration class implements the WebCenterResourceRegistration interface and is correctly registered in the web.xml file.

WCS-64016
Failed to invoke the WebCenter resoruce registration class {0} due to exception {1} with message {2}.

Category:
Other

Cause:
Failed to invoke the WebCenter resource registration class at runtime.

Action:
Make sure the WebCenter resource registration class is correctly implemented and registered in the web.xml file.

WCS-65001
Web service data control creation failed. Check the WSDL and re-create the data control

Category:
Other

Cause:
WSDL may be inaccessible or the WSDL file may be incorrect.

Action:
Make sure the WSDL is accessible and correct, then re-create the data control.

WCS-65002
An unexpected error occurred while creating visualization.

Category:
Other

Cause:
Parameter form not generated.

Action:
Check the logs for exception.

WCS-69251
{0} of {1} is out-of-bounds

Category:
Other

Cause:
Page is not responding within configured limits

Action:
Check the regions on the page to identify which region is problematic, or general system health

WCS-69252
{0} of {1} is out-of-bounds

Category:
Other

Cause:

Action:

WCS-69253
{0} of {1} is out-of-bounds.

Category:
Other

Cause:
Portlet is not responding within configured limits

Action:
Check the backend Producer or the network connectivity to it, or general system health

WCS-69254
{0} of {1} is out-of-bounds

Category:
Other

Cause:
Document Library Upload service is not responding within configured limits

Action:
Check the Content Server or the network connectivity to it, or general system health

WCS-69255
{0} of {1} is out-of-bounds

Category:
Other

Cause:
Document Library Download service is not responding within configured limits

Action:
Check the Content Server or the network connectivity to it, or general system health

WCS-72001
Missing @PersistProperty, @PersistText, @PersistCollection or @PersistReference annotation on method: {0}.

Category:
Other

Cause:
@PersistProperty, @PersistText, @PersistCollection or @PersistReference annotation is required on the accessors corresponding to persistence methods to enable access through the Portal Core Persistence Layer.

Action:
Add the @PersistProperty, @PersistText, @PersistCollection or @PersistReference annotation to the accessor as defined in the Portal Core Persistence Layer's integration documentation.

WCS-72002
PersistenceManager does not support method: {0}.

Category:
Other

Cause:
An attempt was made to use a method that is not supported by the Portal Core Persistence Layer.

Action:
Add the required method to the class.

WCS-72003
Invalid value passed to reference operation "{0}" for reference "{1}". Expected {2}, received {3}.

Category:
Other

Cause:
A value passed to a reference mutator could not be converted to the required type.

Action:
Modify calling code to ensure references are only updated with valid types.

WCS-72004
Cannot instantiate object using abstract PortalEntity interface: {0}

Category:
Other

Cause:
An attempt was made to create a PortalEntity object using an interface that is marked as abstract.

Action:
Supply a non-abstract type or remove the @AbstractEntity annotation from this interface.

WCS-72005
Unable to delete null {0}.

Category:
Other

Cause:
A null PortalEntity or PortalEntityObject was supplied.

Action:
Supply a non-null PortalEntity or PortalEntityObject.

WCS-72006
Unable to delete PortalEntity. A PortalEntity in portal "{0}" and namespace "{1}" with name "{2}" was not found.

Category:
Other

Cause:
An attempt was made to delete a PortalEntity object that does not exist.

Action:
Ensure that the supplied portal, namespace and name values are correct.

WCS-72007
Unable to delete PortalEntity. A PortalEntity with ID "{0}" was not found.

Category:
Other

Cause:
An attempt was made to delete a PortalEntity object that does not exist.

Action:
Ensure that the supplied ID is correct.

WCS-72008
PortalEntity in portal "{0}" and namespace "{1}" with name "{2}" was found but is not of the requested type. Type requested = {3}, type found = {4}.

Category:
Other

Cause:
The type of PortalEntity object found in the persistence store was not as expected.

Action:
Ensure that the supplied portal, namespace, name and type parameters are correct.

WCS-72009
PortalEntity object with ID "{0}" was found but is not of the requested type. Type requested = {1}, type found = {2}.

Category:
Other

Cause:
The type of PortalEntity object found in the persistence store was not as expected.

Action:
Ensure that the supplied ID and type parameters are correct.

WCS-72010
An error occurred while starting a transaction.

Category:
Other

Cause:
An error occurred while starting a transaction.

Action:
Check the root cause of the exception.

WCS-72011
An error occurred while committing a transaction.

Category:
Other

Cause:
An error occurred while committing a transaction.

Action:
Check the root cause of the exception.

WCS-72012
An error occurred while rolling-back a transaction.

Category:
Other

Cause:
An error occurred while rolling-back a transaction.

Action:
Check the root cause of the exception.

WCS-72013
An error occurred while checking the status of a transaction.

Category:
Other

Cause:
An error occurred while checking the status of a transaction.

Action:
Check the root cause of the exception.

WCS-72014
Unable to read the value of property "{0}" of PortalEntity "{1}" using method "{2}".

Category:
Other

Cause:
An error occurred while trying to read a property of a PortalEntity object.

Action:
Use the associated exception to determine why the property could not be read.

WCS-72015
Unable to create XML document.

Category:
Other

Cause:
An error occurred while using JAXB to create an XML document.

Action:
Use the associated exception to determine why JAXB serialization failed.

WCS-72018
Unable to read XML document.

Category:
Other

Cause:
An error occurred while using JAXB to read an XML document.

Action:
Use the associated exception to determine why JAXB deserialization failed.

WCS-72019
Unable to set the value of property "{0}" for PortalEntity "{1}" using method "{2}".

Category:
Other

Cause:
An error occurred while trying to set a property of a PortalEntity object.

Action:
Use the associated exception to determine why the property could not be set.

WCS-72020
Unable to find set method for property "{0}" of PortalEntity "{1}".

Category:
Other

Cause:
An error occurred while trying to set a property of a PortalEntity object.

Action:
Unable to find set method for the property.

WCS-72021
Unable to set references for "{0}" of property "{1}" for PortalEntity "{2}".

Category:
Other

Cause:
An error occurred while trying to set a reference property of a PortalEntity object.

Action:
Use the associated exception to determine why the property could not be set.

WCS-72022
Unsupported data type: {0}.

Category:
Other

Cause:
A data type has been used for a persisted property of an object which is not supported by the Portal Core Persistence Layer.

Action:
Use a data type specified by the oracle.webcenter.portal.persistence.PersistedDataType enum.

WCS-72023
Invalid offset {0} for data type {1}

Category:
Other

Cause:
The offset used for a persisted property is not valid.

Action:
Try using a smaller offset value, if possible.

WCS-72024
PortalEntity object with short ID "{0}" was found but is not of the requested type. Type requested = {1}, type found = {2}.

Category:
Other

Cause:
The type of PortalEntity object found in the persistence store was not as expected.

Action:
Ensure that the supplied short ID and type parameters are correct.

WCS-72025
Unable to delete PortalEntity. A PortalEntity with short ID "{0}" was not found.

Category:
Other

Cause:
An attempt was made to delete a PortalEntity object that does not exist.

Action:
Ensure that the supplied short ID is correct.

WCS-72026
A PortalEntity object with ID "{0}" and name "{1}" was found but is not of the expected type. Type expected = {2}, type found = {3}.

Category:
Other

Cause:
The type of a PortalEntity object found in the persistence store was not as expected.

Action:
Ensure that the type requested in the query is correct.

WCS-72027
Invalid pagination requested in query: Row limit {0}, first row {1}.

Category:
Other

Cause:
Invalid criteria specified for query pagination.

Action:
Ensure that the row limit is greater than zero, and the first row index is greater than or equal to zero.

WCS-72028
Permission class "{0}" cannot be used with actions "{1}".

Category:
Other

Cause:
The permission class name and actions specified via an @Authorization annotation on a PortalEntity class cannot be used with the current security manager.

Action:
Correct the permission class name or actions.

WCS-72029
Could not find permission class named: "{0}".

Category:
Other

Cause:
A permission class specified by the permissionClassName element of an @Authorization annotation could not be loaded.

Action:
Ensure that the name of the class is correct.

WCS-72030
Type "{0}" is not valid. More than one property has datatype {1} and offset {2}, see methods: {3} and {4}.

Category:
Other

Cause:
A type makes incorrect use of the @PersistProperty annotation.

Action:
Use a different offset for one of the methods named in the error message.

WCS-72031
Could not find the persistence object with ID {0} and type {1} in the persistent store.

Category:
Other

Cause:
A PortalEntity was passed to the PersistenceManager but does not correspond to an entity in the persistent store.

Action:
Requery the PortalEntity and try the operation again.

WCS-72032
Invalid from-clause for the query. You must specify one or more types.

Category:
Other

Cause:
The Query.from(Class... types) method was called with either a null or empty list of types.

Action:
Update the code to pass one or more types to the Query.from(Class... types) method.

WCS-72033
The query contains an invalid reference to property {0}.

Category:
Other

Cause:
An invalid property name has been specified in the query.

Action:
Update the query to correct the error.

WCS-72034
The property {0} cannot be used for a property comparsion in a query.

Category:
Other

Cause:
The property type does not implement the Comparable interface and so cannot be used in with an operation that requires a Comparable interface.

Action:
Update the query to correct the error.

WCS-72035
The property {0} is not indexed and so cannot be used in a query without enabling the unindexed property mode.

Category:
Other

Cause:
The property maps to a column that was not marked as indexed and the unindexed property mode is not enabled.

Action:
Either use a different property in the query or enable the unindexed property mode for the query.

WCS-72036
The property {0} cannot be used in the order-by clause of the query.

Category:
Other

Cause:
An invalid property was used in an order-by clause.

Action:
Update the query to use a valid property for the order-by clause.

WCS-72037
Could not set the value of the long text field because the CLOB has not been created.

Category:
Other

Cause:
There has been an attempt to set the value of the long text field before the CLOB has been created.

Action:
Update the calling code to create the CLOB before setting the long text field.

WCS-72038
Cannot import "{1}" resource "{0}" as the target portal is not set and the source portal is not part of the export set

Category:
Other

Cause:
Resource import failed because the portal ID associated with the resource did not match any portal in the target portal server, or the specified portal was not part of the export set, or the target portal was not set on the importXML() method.

Action:
Update the importXML() method to specify a valid portal on the target.

WCS-72039
The target portal for the import does not exist on the portal server.

Category:
Other

Cause:
Import failed as the target portal does not exist on the portal server.

Action:
Update the importXML() method to specify a valid portal on the target.

WCS-72040
The text property getter method {0} has an invalid return type {1}.

Category:
Other

Cause:
The getter method for the text property has a return type that is neither String nor java.io.Reader.

Action:
Update the method to return either String or java.io.Reader.

WCS-72041
The text property setter method {0} has an invalid parameter {1}.

Category:
Other

Cause:
The first parameter of the setter method for the text property is neither String nor java.io.Reader.

Action:
Update the method so that the first parameter is a String or java.io.Reader.

WCS-72042
An attempt was made to create a PortalEntity object named "{0}" and type "{1}" with a null Portal property.

Category:
Other

Cause:
PortalEntities must specify a Portal on creation, unless the type of PortalEntity is a Portal.

Action:
Ensure that a Portal is set on the PortalEntity object prior to creation.

WCS-72043
An attempt was made to set a PortalEntity object named "{0}" and type "{1}" with a null Portal property.

Category:
Other

Cause:
PortalEntities must not specify null as the Portal property on a set operation, unless the type of PortalEntity is a Portal.

Action:
Ensure that a null is not set on the PortalEntity, unless the type of PortalEntity is a Portal.

WCS-72044
Failed to set collection "{0}" of type "{1}" for PortalEntity object of type "{2}" on import.

Category:
Other

Cause:
Collections of this type are not supported.

Action:
Ensure that the data being imported is compatible with this version of the portal server.

WCS-72045
While importing object "{0}" with ID "{1}", could not find referenced object with ID "{2}" (reference name "{3}").

Category:
Other

Cause:
An object referenced by an object in the export set could not be found on the target server.

Action:
If required, transfer the referenced object from the source server to the target server.

WCS-72046
While importing object "{0}" with ID "{1}", could not find referencing object with ID "{2}" and type "{3}" (reference name "{4}").

Category:
Other

Cause:
An object referencing an object in the export set could not be found on the target server.

Action:
If required, transfer the referencing object from the source server to the target server.

WCS-72047
Unable to copy a Portal because a Portal with the name "{0}" already exists.

Category:
Other

Cause:
An attempt was made to copy a Portal with the name of an existing Portal.

Action:
Ensure that the supplied Portal name is unique.

WCS-72048
The targetPortal parameter must be null when copying a Portal.

Category:
Other

Cause:
An attempt was made to copy a Portal with the targetPortal parameter set to a none-null value.

Action:
Ensure that the targetPortal parameter is set to null.

WCS-72049
The current user is not authorized to perform action "{2}" on object {0} ({1}).

Category:
Other

Cause:
The current user does not have permission to perform an action on an object.

Action:
Ensure that the user is granted appropriate permissions.

WCS-72050
A conflict has occurred with your edit, it will be necessary to resubmit the changes using the updated resource.

Category:
Other

Cause:
An optimitistic locking exception was raised by the persistence store, due to an earliuer update on the resource by another transaction.

Action:
Re-try your edits using the updated resource.

WCS-72051
Attempted to apply a security ID {0} on an entity {1} with no Authorization annotation (type {2})

Category:
Other

Cause:
Either setSecurityId() or setSecurityEntity() was called on this entity with a non-null value, but the type of this entity has no Authorization annotation defined.

Action:
Modify the type definition to add the Authorization annotation, or avoid securing this entity type.

WCS-72052
The current user is not authorized to create an object of type "{0}" in portal with ID "{1}"..

Category:
Other

Cause:
The current user does not have permission to create objects of the specified type.

Action:
Ensure that the user is granted appropriate permissions.

WCS-72053
Permission class "{0}" cannot be used with actions "{1}" in @CreateAuthorization annotation.

Category:
Other

Cause:
The permission class name and actions specified via a @CreateAuthorization annotation on a PortalEntity class cannot be used with the current security manager.

Action:
Correct the permission class name or actions.

WCS-72054
An error occurred while setting the timeout of a transaction.

Category:
Other

Cause:
An error occurred while setting the timeout of a transaction.

Action:
Check the root cause of the exception.

WCS-72055
The user is not authorized to perform this operation.

Category:
Other

Cause:
The user was not authorized to perform the operation.

Action:
Check the root cause of the exception for further details.

WCS-72056
A PortalEntity could not be created from PortalEntityObject {0} because no type factories could be found.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-72057
None of the available type factories were able to create a PortalEntity from PortalEntityObject {0}.

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-72058
The EntityManager's transaction is already active.

Category:
Other

Cause:
An error occurred initializing the TransactionManager.

Action:
Modify calling code to remove direct acces to the Portal EntityManager's transaction.

WCS-72059
The EntityManager is configured for JPA.

Category:
Other

Cause:
An error occurred initializing the TransactionManager.

Action:
The Portal EntityManager must be configured for resource local transactions.

WCS-72060
The TransactionManager has uncommitted changes which have been rolled back.

Category:
Other

Cause:
The TransactionManager's context is ending and the uncommitted changes have been rolled back.

Action:
Contact your Oracle Support representative.

WCS-72061
The TransactionManager has uncommitted changes which cannot be rolled back.

Category:
Other

Cause:
The TransactionManager's context is ending and rollback of its uncommitted changes has failed.

Action:
Check the root cause of the exception and contact your Oracle Support representative.

WCS-72062
The TransactionManager cannot begin the transaction as the EntityManager's transaction is already active.

Category:
Other

Cause:
The EntityManager's transaction is already active.

Action:
Ensure that no calling code is directly accessing the Portal EntityManager's transaction.

WCS-72063
The TransactionManager must fully rollback.

Category:
Other

Cause:
All outstanding transactions must be rolled-back.

Action:
Rollback all outstanding transactions.

WCS-72064
An error occurred executing a transactional method.

Category:
Other

Cause:
An error occurred executing a transactional method.

Action:
Check the root cause of the exception.

WCS-72065
Transactions cannot be commited out of order.

Category:
Other

Cause:
The calling code is attempting to commit transactions out of order.

Action:
The calling code must commit transactions in the same order as they were begun.

WCS-72067
Failed to set translation "{0}" for Locale "{1}" on PortalEntity object of type "{2}" on import.

Category:
Other

Cause:
An error occurred while trying to set a property of a PortalEntity object.

Action:
Use the associated exception to determine why the property could not be set.

WCS-72068
None of the available factories are able to create an instance of type "{0}".

Category:
Other

Cause:
An internal error occurred.

Action:
Contact Oracle Support Services.

WCS-72401
Cannot determine the ID of the current page. The current page will not be available via the Portal Request Context.

Category:
Other

Cause:
The Portal Runtime Framework was unable to obtain the ID of the current page using JSF.

Action:
Ensure that the application is running in a JSF environment.

WCS-72402
Cannot find a page with ID "{0}". The current page will not be available via the Portal Request Context.

Category:
Other

Cause:
The current page with the given ID could not be found in the Portal's persistent store.

Action:
Ensure that the page with the given ID is present in the Portal's persistent store.

WCS-72403
The AdfPortalController Failed to redirect to URL "{0}".

Category:
Other

Cause:
An internal error occurred whilst attempting to perform a redirect of the portal.

Action:
Contact Oracle Support Services.

WCS-72404
Could not load policy factory of type: {0}

Category:
Other

Cause:
No policy factory classes of the given type could be found.

Action:
Contact Oracle Support Services.

WCS-72405
PortalExternalContext accessed when the PortalExternalContext stack is empty.

Category:
Other

Cause:
A PortalExternalContext must be pushed on to the context stack before it is first accessed.

Action:
Contact Oracle Support Services.

WCS-72501
Unable to find the CDI bean for type: {0}.

Category:
Other

Cause:
No beans of the given type are available for injection.

Action:
Make sure that an injectable implementation of the given type is on the classpath.

WCS-72551
Method "{0}" cannot be called when the current transaction is active.

Category:
Other

Cause:
A method with a Transactional annotation whose propagation element was set to NEVER was called when a transaction was active.

Action:
Make sure the transaction is not active when the method is called.

WCS-72552
Method "{0}" must be called when the current transaction is active.

Category:
Other

Cause:
A method with a Transactional annotation whose propagation element was set to MANDATORY was called when a transaction was not active.

Action:
Make sure the transaction is active when the method is called.

WCS-72571
Cache name "{0}" is invalid.

Category:
Other

Cause:
An invalid cache name has been used.

Action:
Make sure the cache name is of the form "oracle.webcenter.*".

WCS-72601
Failed to create a document with Metadata Object absolute name "{0}".

Category:
Other

Cause:
An underlying MDS exception caused this.

Action:
See related log entries.

WCS-72602
Metadata Object absolute name "{0}" already exists.

Category:
Other

Cause:
Metadata already exists.

Action:
Check the metadata to be created.

WCS-72603
Pattern syntax error in name "{0}".

Category:
Other

Cause:
Pattern syntax error in name.

Action:
Check name.

WCS-72604
Metadata Object absolute name "{0}" not found.

Category:
Other

Cause:
Metadata not found.

Action:
Check the metadata to be found.

WCS-72605
Encountered an MDS exception "{0}" with message "{1}".

Category:
Other

Cause:
An underlying MDS exception caused this.

Action:
Check underlying exception.

WCS-72608
Failed to update a Portal object.

Category:
Other

Cause:
An underlying exception caused this.

Action:
Check underlying exception.

WCS-72609
Failed to delete a Portal object.

Category:
Other

Cause:
An underlying exception caused this.

Action:
Check underlying exception.

WCS-72610
Required parameter {0} not specified.

Category:
Other

Cause:
Required parameter is not specified.

Action:
Ensure that the required parameter is specified.

WCS-72611
Required parameters {0} and/or {1} not specified.

Category:
Other

Cause:
Required parameters are not specified.

Action:
Ensure that the required parameters are specified.

WCS-72612
File type is required for paramter {0}

Category:
Other

Cause:
File type is not specified in the parameter.

Action:
Ensure that the file type is specified.

WCS-72613
A version conflict was detected when updating the portal object. {0}

Category:
Other

Cause:
The supplied PropertyBean has a non-null currentVersionId property, and it does not match the current version ID of the object it was applied to.

Action:
Requery the portal object properties and apply the update again if appropriate.

WCS-72615
PropertyBean create validation failed: {0}

Category:
Other

Cause:
The supplied PropertyBean violates the validation constraints that are enforced for creation with this type of PropertyBean.

Action:
Review the error message for details of the constraint violations.

WCS-72616
PropertyBean update validation failed: {0}

Category:
Other

Cause:
The supplied PropertyBean violates the validation constraints that are enforced for update with this type of PropertyBean.

Action:
Review the error message for details of the constraint violations.

WCS-72620
ValidationFrame not populated.

Category:
Other

Cause:
The ValidationFrame providing context for PropertyBean validation did not contain state that was expected to be present.

Action:
Contact Oracle Support Services.

WCS-72621
FrameAwareValidator invoked outside of a ValidationFrame.

Category:
Other

Cause:
The ValidationFrame providing context for PropertyBean validation was not found.

Action:
Contact Oracle Support Services.

WCS-72622
Error getting bean value.

Category:
Other

Cause:
Inspect the cause exception to determine the underlying cause.

Action:
Contact Oracle Support Services.

WCS-72624
An error occurred while attempting to copy the portlets.

Category:
Other

Cause:
An exception was thrown while attempting to copy the portlets for a page.

Action:
Check the root cause of the exception.

WCS-72625
An error occurred while trying to instantiate the query manager or named query via reflection.

Category:
Other

Cause:
An exception was thrown while attempting to load query classes via reflection.

Action:
Check that the classes requested are valid for this operation.

WCS-72627
The asset of the given Id {0} is not found.

Category:
Other

Cause:
The asset is not found.

Action:
Check that the asset with the given Id value exists.

WCS-72628
Duplicate name: {0}.

Category:
Other

Cause:
An attempt was made to create an object with a name that has already been used.

Action:
Use a different name.

WCS-72629
Duplicate portal name: {0}.

Category:
Other

Cause:
An attempt was made to create a portal with a name that has already been used for a portal.

Action:
Use a different name for the portal.

WCS-72632
Device Operation {0} not allowed.

Category:
Other

Cause:
Devices and Device Groups cannot be created, modified or deleted in a custom portal

Action:
Ensure that the operations are performed at the portal server

WCS-72633
Device group {0} being customized in {1} portal does not exist at the portal server

Category:
Other

Cause:
Device group being customized at the portal level does not exist

Action:
Ensure that device group being customized exists in the portal server

WCS-72637
Authorization failure when trying to delete {0} type object "{1}" with ID: {2}

Category:
Other

Cause:
The current user is not authorized to delete the object

Action:
Ensure that the user is granted the appropriate permissions

WCS-72638
Authorization failure when trying to update {0} type object "{1}" with ID: {2}

Category:
Other

Cause:
The current user is not authorized to update the object

Action:
Ensure that the user is granted the appropriate permissions

WCS-72639
The Portal API object is not attached.

Category:
Other

Cause:
The Portal API object has a null id. This means it is not attached to any underlying persistence object.

Action:
The Portal API client should attach the object or obtain a new object with a valid id from the PortalObjectRepository. The object can become unattached if it has been deleted.

WCS-72640
The persistence resource with ID "{0}" associated with the ManagedPortalObject could not be found.

Category:
Other

Cause:
The Portal API ManagedPortalObject object is attached to an underlying persistence resouce that is no longer available.

Action:
The Portal API client should take appropriate action to account for the deleted Portal API object.

WCS-72641
There was a failure adding member "{0}" to portal "{1}"

Category:
Other

Cause:
A failure occurred adding a member to a portal.

Action:
Examine the logged exception for more details.

WCS-72642
There was a failure removing member "{0}" from portal "{1}"

Category:
Other

Cause:
A failure occurred removing a member from a portal.

Action:
Examine the logged exception for more details.

WCS-72643
There was a failure removing members for role "{0}" from portal "{1}"

Category:
Other

Cause:
A failure occurred removing all members with a role from a portal.

Action:
Examine the logged exception for more details.

WCS-72646
Duplicate portal display name: {0}.

Category:
Other

Cause:
An attempt was made to create a portal with a display name that has already been used for a portal.

Action:
Use a different display name for the portal.

WCS-72647
Null portal name.

Category:
Other

Cause:
An attempt was made to create a portal with a null name.

Action:
Use a non-null name for this portal.

WCS-72648
Null portal display name.

Category:
Other

Cause:
An attempt was made to create a portal with a null display name.

Action:
Use a non-null display name for this portal.

WCS-72649
Operation forbidden without authorization to perform action {0} on {1} (type {2}, id {3})

Category:
Other

Cause:
An attempt was made to perform an unauthorized action.

Action:
Ensure user is authorized to perform this action and retry.

WCS-72650
Invalid name: {0}.

Category:
Other

Cause:
An attempt was made to create an object with a invalid name.

Action:
Use a different valid name.

WCS-72651
Invalid portal name: {0}.

Category:
Other

Cause:
An attempt was made to create a portal with a invalid name.

Action:
Use a name containing only letters and digits.

WCS-72652
Invalid portal template name: {0}.

Category:
Other

Cause:
An attempt was made to create a portal template with a invalid name.

Action:
Use a name containing only letters and digits.

WCS-72653
Failed to rename a Portal object.

Category:
Other

Cause:
An underlying exception caused this.

Action:
Check underlying exception.

WCS-72654
Unable to cleanup properly after failed creation of {0}.

Category:
Other

Cause:
An underlying exception caused this.

Action:
Check underlying exception.

WCS-72655
Some properties have violated their constraints.

Category:
Other

Cause:
Constrainst have been violated on setting or updating the properties.

Action:
Check that the properties values are correct.

WCS-72656
The combination of (isDiscoverable=false and isPublic=true) is not allowed.

Category:
Other

Cause:
The Access Level setting constraint has been violated.

Action:
Check that the properties values are correct.

WCS-72657
Operation is forbidden.

Category:
Other

Cause:
The operation is forbidden.

Action:
Do not attempt this operation.

WCS-72658
Cannot copy service {0} from {1} to {2}, as service not provisioned in {1}.

Category:
Other

Cause:
The service cannot be copied as it is not provisioned in the source portal.

Action:
Exclude the service from the portal copy request.

WCS-72659
Attempt to modify or delete seeded object {0}. Seeded objects cannot be modified or deleted.

Category:
Other

Cause:
Seeded objects cannot be modified or deleted.

Action:
None

WCS-72660
A failure occurred during MDS document contents substitution.

Category:
Other

Cause:
An underlying exception caused this.

Action:
Check underlying exception.

WCS-72661
Unable to cleanup properly after failed deletion of {0}.

Category:
Other

Cause:
An underlying exception caused this.

Action:
Check underlying exception.

WCS-72662
Unable to copy resource bundle documents for portal : {0}.

Category:
Other

Cause:
An underlying exception caused this.

Action:
Check underlying exception.

WCS-72663
Invalid display name: {0}.

Category:
Other

Cause:
An attempt was made to create an object with a invalid display name.

Action:
Use a different valid display name.

WCS-72664
Invalid portal display name: {0}.

Category:
Other

Cause:
An attempt was made to create a portal with a invalid display name.

Action:
Use a display name containing only letters and digits.

WCS-72701
Error in checking if the service ${0} is provisioned for portal ${1}.

Category:
Other

Cause:
Unable to discover the service's provisioning status.

Action:
Examine the exception for further information.

WCS-72702
Error in checking which services are configured.

Category:
Other

Cause:
Unable to discover which services are configured.

Action:
Examine the exception for further information.

WCS-72703
Error in provisioning service ${0} for portal ${1}.

Category:
Other

Cause:
Unable to provision the service for the portal.

Action:
Examine the exception for further information.

WCS-72704
Error in unprovisioning service ${0} for portal ${1}.

Category:
Other

Cause:
Unable to unprovision the service for the portal.

Action:
Examine the exception for further information.

WCS-72705
Error in retrieving the ScopeAPI for the ${0} service.

Category:
Other

Cause:
Unable to get the ScopeAPI for the service.

Action:
Examine the exception for further information.

WCS-72706
Error getting group info for user ${0}.

Category:
Other

Cause:
Unable to get group info for a user.

Action:
Examine the exception for further information.

WCS-72707
Error in copying service ${0} from portal ${1} to portal {2}.

Category:
Other

Cause:
Unable to unprovision the service for the portal.

Action:
Examine the exception for further information.

WCS-72801
Error publishing activity to the activity stream

Category:
Other

Cause:
Unable to publish an activity to the activity stream.

Action:
Examine the exception for further information.

WCS-72802
The {2} role has already been granted for user {1} in portal {0}

Category:
Other

Cause:
Unable to grant the role because it has already been granted.

Action:
Examine the exception for further information.

WCS-72803
Failed to grant the {2} role for user {1} in portal {0}

Category:
Other

Cause:
Unable to grant the role due to an exception.

Action:
Examine the exception for further information.

WCS-72804
Failed to revoke the {2} role for user {1} in portal {0}

Category:
Other

Cause:
Unable to revoke the role due to an exception.

Action:
Examine the exception for further information.

WCS-72805
Failed to set permissions for portal {0}

Category:
Other

Cause:
Unable to set permissions due to an exception.

Action:
Examine the exception for further information.

WCS-72806
Failed to drop role {0} for portal {1}

Category:
Other

Cause:
Unable to drop role due to an exception.

Action:
Examine the exception for further information.

WCS-72807
Failed to to set permission actoins for role {0} for portal {1} on member {2}

Category:
Other

Cause:
Unable to set a member's permission actions for a role due to an exception.

Action:
Examine the exception for further information.

WCS-72808
Failed to to create translation bundle for portal {0}

Category:
Other

Cause:
Unable to create translation bundle due to an exception.

Action:
Examine the exception for further information.

WCS-72901
The method {0} is not supported

Category:
Other

Cause:
A method that is not supported has been called.

Action:
Update the application to use another method.

WCS-73000
Muffling exception.

Category:
Other

Cause:
An error occurred but processing was allowed to continue.

Action:
Use the context information to determine if remedial action is required.

WCS-73001
Unable to instantiate upgrade handler {0}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
Make sure that handler implementation is on the classpath.

WCS-73002
Unable to instantiate upgrade manager.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73003
Upgrade failed for portal {0}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73004
Upgrade clean up failed for portal {0}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73005
Upgrade initialization failed for handler {0}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73006
Upgrade validation failed for {0}:{1} in scope {2}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73007
Upgrade validation failed for {0}:{1} in scope {2} due to : {3}.

Category:
Other

Cause:
Validation failed for the said cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73008
Upgrade phase failed for {0}:{1} in scope {2}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73009
Upgrade clean up failed for {0}:{1} in scope {2}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73010
Post upgrade failed for {0}:{1} in scope {2}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73011
Portal {0} with id {1} not found in the repository.

Category:
Other

Cause:
Either the portal upgrade has not happened or there is some data corruption.

Action:
Check logs for related error. Re-run upgrade. If you still continue to see the issue, contact Oracle Support Services.

WCS-73012
Default portal upgrade failed therefore halting the upgrade.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run upgrade. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73013
Exception while resolving the reference for {0} , message: {1}.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run upgrade. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73014
Exception while getting a list of scopes for upgrade, message: {0}.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run upgrade. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73015
Exception while getting a list of scopes for clean up, message: {0}.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run upgrade. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73016
Exception while persisting the information related to upgrade scope failure, message: {0}.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run upgrade. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73017
An error occurred while trying to audit portal server using MDS root {0}.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run audit. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73018
An error occurred while trying to generate audit report for portal server in report directory {0}.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run audit. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73019
An error occurred while trying to audit portals {0} using MDS root {1}.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run audit. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73020
An error occurred while trying to generate audit report for portals {0} in report directory {1}.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run audit. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73021
An error occurred while trying to initialize mbeans to audit deprecated connection usage.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run audit. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73022
An error occurred while trying to audit deprecated connection usage.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run audit. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73023
An error occurred while trying to audit deprecated usage of type {0} in scopes {1}.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run audit. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73024
Exception while getting a list of scopes for post upgrade, message: {0}.

Category:
Other

Cause:
Review the related exception in the logs to determine the cause.

Action:
Re-run upgrade. If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73025
Post upgrade failed for portal {0}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73026
Unable to instantiate Upgrade Context for scope {0}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73027
An error occurred while upgrade.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73028
Could not find scope having identifier {0} while auditing {1} with path {2}

Category:
Other

Cause:
This looks like a case of data corruption where scope does not exist for a resource

Action:
Review list of portals in the Portal Server and see if you can find the required portal or any logs pertaining to its failure. Otherwise contact Oracle Support Services.

WCS-73029
Unable to update the audit data for the resources of scope {0}.

Category:
Other

Cause:
An error occurred applying the audit data.

Action:
No action may be required if this information is not deemed as important, otherwise if the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73030
Unable to update the audit data for the resource with id {0} of scope {1}.

Category:
Other

Cause:
An error occurred applying the audit data.

Action:
No action may be required if this information is not deemed as important, otherwise if the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73031
Failed to delete data file ({0}) associated with the audit data for scope {1}.

Category:
Other

Cause:
An error occurred deleteing the audit data file.

Action:
If the exception details do not provide sufficient information to resolve the issue. However, this failure is unlikely to affect the success of the upgrade.

WCS-73032
One or more scopes failed to have audit data columns updated, e.g. Portal last updated by and updated date information.

Category:
Other

Cause:
An error occurred during audit column data update.

Action:
No action may be required if this information is not deemed as important, otherwise see if the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73033
The upgrade process was unable to create a directory ({0}) required to persist upgrade data during the upgrade process.

Category:
Other

Cause:
An error occurred during directory creation.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73034
The upgrade process was unable to read the audit column data file ({0}) for scope {1}.

Category:
Other

Cause:
An error occurred during an attempt to read the audit column datafile.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73035
The upgrade process was unable to create a file ({0}) required to persist upgrade data during the upgrade process.

Category:
Other

Cause:
An error occurred during file creation.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73036
Could not find the devices data file in the MDS repository. No devices and device groups will be migrated.

Category:
Other

Cause:
The instance being upgraded is probably release 11.1.1.7.0 or earlier where the device support feature did not exist.

Action:
If the instance being upgraded is release 11.1.1.7.0 or earlier, this is expected and can be safely ignored.

WCS-73037
Upgrade of portal {0} encountered a custom attribute named {1} with the following value exceeding the limit of 2000 characters : {2}

Category:
Other

Cause:
A large value has been set for a custom attribute which exceeds the size limit for upgraded Portal's custom attributes.

Action:
If this attribute is required in the upgraded Portal attempt to use a value of less than 2000 characters, or find another mechanism to handle the requirements which does not utilize the custom attribute mechanism.

WCS-73038
Error while trying to determine whether default scope upgrade succeeded

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73039
Default Scope cleanup is not attempted due to existing failures in other scopes

Category:
Other

Cause:
A few scopes have failed during upgrade. Default Scope cleanup is not attempted until all other scopes pass upgrade

Action:
Address the existing failures and run the upgrade process again.

WCS-73040
Portal Members not copied to Moderator role for portal {0}

Category:
Other

Cause:
There may not be any portal members with the moderator role or the member data is corrupted.

Action:
Contact the administrator.

WCS-73041
An error occurred while trying to obtain a list of members from the moderator role for portal {0}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause. This may be a case of data corruption, where there are no moderators for the portal.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73042
Permissions not copied for Moderator role for portal {0}

Category:
Other

Cause:
Permissions may not be set for the moderator role or the member data is corrupted.

Action:
Contact the administrator.

WCS-73043
An error occurred while trying to obtain permissions for the moderator role for portal {0}.

Category:
Other

Cause:
Review the underlying exception in the logs to determine the cause. This may be a case of data corruption, where the permissions are not set for the moderator role.

Action:
If the exception details do not provide sufficient information to resolve the issue, then contact Oracle Support Services.

WCS-73044
Skipping sub portal security upgrade for portal {0} since security is not inherited for this portal.

Category:
Other

Cause:
Skipping sub portal security handler upgrade since security is not inherited for this portal.

Action:
Check the portal for any data issues.

WCS-73045
Upgrade for scope {0} has not been attempted.

Category:
Other

Cause:
Upgrade may have been halted abruptly.

Action:
Rerun Upgrade again

WCS-89001
An unexpected error occurred in the activity stream sub-system.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-89002
WSRP Connection Name {0} already exists.

Category:
Other

Cause:
Connection Name used already exists.

Action:
Use a different name for the connection.

WCS-89003
Web Service Connection Name {0} already exists. WSRP connection {1} cannot be created.

Category:
Other

Cause:
Connection Name used already exists.

Action:
Use a different name for the connection.

WCS-89004
Cannot register the producer due to connectivity issues.

Category:
Other

Cause:
Failed to connect to the producer. Either the connection details specified were invalid or there was a network problem.

Action:
Verify that the producer connection details are correct, and then check to see if a firewall or some other network issue is blocking the connection.

WCS-89005
Unable to register the producer due to an invalid WSDL URL.

Category:
Other

Cause:
The WSDL URL specified for the WSRP producer was invalid.

Action:
Specify a valid WSDL URL, and then try again.

WCS-89006
URL Connection Name {0} already exists.

Category:
Other

Cause:
Connection Name used already exists.

Action:
Use a different name for the connection.

WCS-89007
Web Producer Name {0} already exists.

Category:
Other

Cause:
Web Producer Name used already exists.

Action:
Use a different name for the Web producer.

WCS-89008
Unable to register the producer due to exception {0}. Contact your administrator.

Category:
Other

Cause:
Error occurred registering the producer.

Action:
Examine the log files for more detail.

WCS-89009
Unable to unregister the producer due to exception {0}. Contact your administrator.

Category:
Other

Cause:
Error occurred deregistering the producer.

Action:
Examine the log files for more detail.

WCS-89010
Unable to get producer connections due to exception {0}. Contact your administrator.

Category:
Other

Cause:
Error occurred retrieving the list of producers.

Action:
Examine the log files for more detail.

WCS-89011
Unable to register the WSRP producer due to exception {0}. Contact your administrator.

Category:
Other

Cause:
Error occurred registering the WSRP producer.

Action:
Examine the log files for more detail.

WCS-89012
Unable to register the JPDK producer due to exception {0}. Contact your administrator.

Category:
Other

Cause:
Encountered an exception when registering the JPDK producer.

Action:
Examine the log files for more detail.

WCS-89013
Unable to create the WSRP producer connection due to exception {0}. Contact your administrator.

Category:
Other

Cause:
Error occurred creating the WSRP producer connection.

Action:
Examine the log files for more detail.

WCS-89014
Unable to refresh the producer connections due to exception {0}

Category:
Other

Cause:
Error occurred refreshing the list of producers.

Action:
Examine the log files for more detail.

WCS-89015
Failed to clean up producer registration due to exception {0}. Contact your administrator.

Category:
Other

Cause:
Error occurred cleaning up the producer registration.

Action:
Examine the log files for more detail.

WCS-89016
The operation failed due to an exception. Contact your administrator.

Category:
Other

Cause:
Error occurred performing the operation.

Action:
Examine the log files for more detail.

WCS-89017
Error parsing policy XML ({0}) from PolicyApplication mbean with message {1}

Category:
Other

Cause:
Error parsing policy XML from PolicyApplication mbean.

Action:
Make sure the policy XML in the PolicyApplication mbean is set correctly.

WCS-89018
Registration of OmniPortlet is not supported

Category:
Other

Cause:
Registration of OmniPortlet is not supported.

Action:
Register any other JPDK Portlet other than OmniPortlet.

WCS-89501
An unexpected error occurred in the activity stream sub-system.

Category:
Other

Cause:
An unexpected error occurred.

Action:
Contact Oracle Support Services.

WCS-89502
External Application Connection Name {0} already exists.

Category:
Other

Cause:
Connection Name used already exists.

Action:
Use a different name for Connection.

WCS-89503
No connection selected for this operation.

Category:
Other

Cause:
No External Application connection selected for this operation.

Action:
Select a External Application connection from the table listing the available connections.

WCS-90100
No moveplan.xml file available.

Category:
Other

Cause:
moveplan.xml file missing.

Action:
Contact Oracle Support Services.

WCS-90200
Error in validating the source environment.

Category:
Other

Cause:
Invalid source environment.

Action:
Contact Oracle Support Services.

38

WSM-00001 to WSM-09029

WSM-00001
A JAXB context for path "{0}" cannot be created due to underlying error "{1}".

Category:
Other

Cause:
The error could have been caused by creating the JAXB2.0 marshaller/unmarshaller.

Action:
Contact Oracle Support Services.

WSM-00002
A class of type {0} cannot be marshaled due to underlying error "{1}".

Category:
Other

Cause:
Error occurred in JAXB marshalling (1.e converting java object to xml.)

Action:
Contact Oracle Support Services or refer to http://java.net/jaxb.

WSM-00003
An element of type {0} cannot be unmarshalled due to underlying error "{1}".

Category:
Other

Cause:
Error occurred while doing JAXB unmarshall i.e converting XML to Java.

Action:
Contact Oracle Support Services.

WSM-00004
WS-Security Exception : {0}

Category:
Security

Cause:
The system encountered a generic failure in security.

Action:
Contact Oracle Support Services.

WSM-00005
Error in sending the request.

Category:
Security

Cause:
Failure occurred while trying to send the request message, possibly due to a failure in security code.

Action:
Retry the operation for a maximum of 3 times. If the problem persists, contact Oracle Support Services.

WSM-00006
Error in receiving the request: {0}.

Category:
Security

Cause:
Failure occurred while processing the request message, possibly due to a failure in security checks.

Action:
Refer to the policy for the expected nature of the request message and retry the operation.

WSM-00007
JPS exception

Category:
Security

Cause:
The error was most likely due to an invalid JPS configuration.

Action:
Correct the JPS configuration and retry the operation.

WSM-00008
Login Exception: {0}.

Category:
Security

Cause:
Login Exception at OPSS.

Action:
Resend valid credentials.

WSM-00009
The password policy does not match. Expected: {0}, Received:{1}.

Category:
Security

Cause:
The expected and actual password types did not match.

Action:
Refer to the policy to determine the allowed password type value.

WSM-00010
Message rejected as the nonce element in the WS-Security header is missing.

Category:
Security

Cause:
Nonce was required according to policy requirements, but was not found.

Action:
Resend the request with valid value of nonce.

WSM-00011
The wsu:Created element is required.

Category:
Security

Cause:
The Created element was required, but was not found.

Action:
Resend the request with valid value of the Created element with the UTC timestamp of the instance in which the request was created.

WSM-00012
The password is ignored, as it is not required by the policy.

Category:
Security

Cause:
The password was sent in the <UsernameToken>, when it was not required.

Action:
The password type prescribed by the policy is None, so password should not be sent.

WSM-00015
The user name is missing.

Category:
Security

Cause:
Username was expected but was not found.

Action:
Either the username element or the username inside the username element is missing. Resend the request with a valid username.

WSM-00016
The username/password credentials or certificates {0} are missing.

Category:
Security

Cause:
It is possible that username/password or certificate is missing.

Action:
Resend valid credentials.

WSM-00017
The <bindings> element for {0}:{1} is missing.

Category:
Configuration

Cause:
It is likely that the bindings element is missing inside policy.

Action:
Re-create the policy with valid bindings.

WSM-00018
There is more than one security header with the same role {0}.

Category:
Security

Cause:
More than one security header was found with the same role associated.

Action:
Refer to the WS-Security 1.0 or 1.1 specifications. Do not send more than one security header having the same role.

WSM-00019
The version of SOAP used is not supported: {0}.

Category:
Requests/Responses

Cause:
An envelope was obtained that conforms to an unsupported version of SOAP.

Action:
Use a supported version. SOAP 1.1 and 1.2 are supported.

WSM-00020
Error sending the response.

Category:
Other

Cause:
A failure occurred while building the response.

Action:
Retry a maximum of three times. If the retry attempts fail, contact Oracle Support Services.

WSM-00021
Error receiving the response.

Category:
Security

Cause:
A failure occurred while processing the response, most likely due to a failure in the security check.

Action:
Retry sending the response to the client.

WSM-00022
Error sending a fault.

Category:
Other

Cause:
A failure occurred while sending the fault.

Action:
Retry for a maximum of three times. If the retry attempts fail, contact Oracle Support Services.

WSM-00023
Error receiving a fault.

Category:
Security

Cause:
A failure occurred while processing the fault, most likely due to a failure in the security check.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-00024
The SAML token is missing from the security header. Ensure that there is a SAML token policy attached on the client side. Tokens found in the security header are :- {0}.

Category:
Security

Cause:
The SAML assertion that was expected inside the security header was not found.

Action:
Insert valid SAML assertions and resend the request.

WSM-00025
SAML token verification failure.

Category:
Security

Cause:
SAML token verification failed.

Action:
Check the validity period of the SAML assertion using Conditions, or determine whether the assertion must be signed. Ensure that the SAML token conforms to the requirements of the SAML 1.0 specification.

WSM-00026
The SAML token cannot be added to the security header.

Category:
Other

Cause:
A failure occurred while adding the SAML token to the security header.

Action:
Check the log file for a possible cause.

WSM-00027
The configuration parameter {0} contains an invalid value [{1}].

Category:
Configuration

Cause:
The configuration settings were invalid.

Action:
Check the configuration and retry the operation.

WSM-00028
Failure in getting user credentials from client.

Category:
Configuration

Cause:
Failure occurred while extracting user credentials from the client side.

Action:
Check Keystore/Username and the Password/CSF configuration.

WSM-00029
The algorithms used to encrypt the data do not match those specified in the policy. : Expected : {0}, Actual : {1}.

Category:
Security

Cause:
The expected and actual data encryption algorithms did not match.

Action:
Check the policy to determine the permitted values for the data encryption algorithm.

WSM-00030
The encryption method key wrap algorithms do not match : Expected : {0}, Actual : {1}.

Category:
Security

Cause:
The expected and actual key wrap encryption algorithms did not match.

Action:
Check the policy to determine the permitted values for the key wrap encryption algorithm. In addition, refer to WS-Security Policy 1.1 for a list of allowed values.

WSM-00031
The digest algorithms do not match.

Category:
Security

Cause:
The actual digest algorithms for the signature did not match the expected algorithms.

Action:
Check the policy to determine the permitted values for the signature digest algorithms.

WSM-00033
The encrypted message elements or parts do not comply with the policy. The following headers/elements (<name space: local name>) or attachments (<attachment ID: attachment type>) must be encrypted:- {0}

Category:
Security

Cause:
Parts or elements to be encrypted according to policy were different from those in the SOAP message.

Action:
Refer to the policy and WS-Security specifications to ensure that all encryption requirements mandated by the policy and the specifications are met.

WSM-00034
Error in Encryption reference mechanism compliance : Expected : {0} , Actual : {1}. Ensure that a compatible policy is attached at the client side.

Category:
Security

Cause:
The expected and actual encryption reference mechanisms did not match.

Action:
Check the policy to determine the permitted values for the encryption reference mechanism.

WSM-00035
Error in Signature reference mechanism compliance : Expected : {0} , Actual : {1}. Ensure that a compatible policy is attached at the client side.

Category:
Security

Cause:
The expected and actual signature reference mechanisms did not match.

Action:
Check the policy to determine the allowed value of the signature reference mechanism.

WSM-00036
The signed message elements or parts do not comply with the policy. The following headers/elements (<name space: local name>) or attachments (<attachment ID: attachment type>) must be signed:- {0}

Category:
Security

Cause:
Parts or elements to be signed according to policy were different from those in the soap message.

Action:
Refer to the policy and WS-Security specifications to make sure that all the signature requirements mandated by the policy and the specifications are met.

WSM-00037
Error in signature confirmation compliance.

Category:
Security

Cause:
The error could have occurred because the response signature confirmation element was not signed.

Action:
Check that all the signature confirmations in the response are signed and referenced in the response signature.

WSM-00039
Message is not compliant with timestamp requirement of the policy. Timestamp element is required by policy but it is not present in the message.

Category:
Security

Cause:
Policy compliance failed due to timestamp. Timestamp element is required by policy but it is not present in the message.

Action:
Check the message and make sure message is compliant with timestamp requirement of the service policy.

WSM-00042
The request must be made over SSL.

Category:
Requests/Responses

Cause:
The request was expected to be sent over SSL, but it was not.

Action:
Check the SSL port and send the request over SSL.

WSM-00043
No peer certificates are present from the HTTP request.

Category:
Security

Cause:
A certificate in the trust chain is missing.

Action:
Ensure that the complete certificate chain is propagated in the request, if certificates signed by CA are used.

WSM-00044
The HTTP authorization header is missing.

Category:
Security

Cause:
The authorization Header was not found.

Action:
Ensure that the request HTTP headers contain an authorization header.

WSM-00045
HTTP authentication/authorization failure.

Category:
Security

Cause:
Failure occurred in basic authentication.

Action:
Use the appropriate Base64 encoded combination of a valid username and password.

WSM-00046
Error in advertisement of WS-Policy.

Category:
Other

Cause:
An error occurred while advertising ORAWSDL to WS-Policy.

Action:
Contact Oracle Support Services.

WSM-00047
Invalid key referencing mechanism: {0}.

Category:
Configuration

Cause:
The sign or encryption key reference mechanism used was invalid.

Action:
Valid supported values are direct, issuerserial, SKI, or thumbprint.

WSM-00048
The signature confirmation value is invalid. Expected : {0}, Actual : {1}.

Category:
Security

Cause:
Signature confirmation sent in the response was invalid.

Action:
See the WS-Security 1.1 specification for the correct @Value of SignatureConfirmation.

WSM-00049
The expected {0} signature is missing in the request message.

Category:
Security

Cause:
No signature (message, or endorsing) was found in the request to confirm.

Action:
Resend the request with at least one <Signature>.

WSM-00050
Cannot obtain security token reference.

Category:
Other

Cause:
The message was not signed or encrypted properly.

Action:
Check the <ds:Reference> section of the message.

WSM-00051
The encrypted data or key cannot be obtained.

Category:
Other

Cause:
The referenced encrypted object could not be found. The referenced encrypted object could not be found.

Action:
Ensure that the reference points to valid <EncryptedData> element. Ensure that the reference points to valid <EncryptedKey> element.

WSM-00052
There is an invalid or nonexistent configuration for the Login Module class [{1}] in the Java Platform Security (JPS) context [{0}].

Category:
Configuration

Cause:
An invalid or nonexistent configuration for Login Module could have been used.

Action:
Change the configuration and retry the operation.

WSM-00053
The propagated subject is either null or empty.

Category:
Security

Cause:
No Subject was found.

Action:
Send a valid nonempty Subject.

WSM-00054
The password credentials cannot be obtained from the Credential Store Framework (CSF). Unable to retrieve the csfKey "{0}". The csf map "{1}" found in the credential store is being used and the following keys are found in this map <CsfKeyName: UserName>:- {2}

Category:
Configuration

Cause:
Failure occurred while doing query for credentials from Credential Store Framework (CSF).

Action:
Check CSF configuration.

WSM-00055
The keystore located at {0} cannot be loaded due to {1}. Ensure that valid keystore type and password are configured.

Category:
Configuration

Cause:
The following keystore-related configuration properties may not be valid:keystore.type, keystore.pass. Also, the keystore could be corrupt or could have been tampered with.

Action:
Verify the configuration properties mentioned above and retry the operation. In a rare situation, replace or regenerate the keystore.

WSM-00056
The key, {0}, is not retrieved. Ensure that the above key exists in the credential store. The location of the key store being used is "{1}" and its type is "{2}". The following aliases are found in the keystore:- {3}

Category:
Configuration

Cause:
Error occurred while obtaining key from store.

Action:
Make sure the key exists in the keystore. Check JPS configuration settings for correct key alias, key password and keystore password. Also, check the values of the key keystore-csf-key and its password in the oracle.wsm.security map, through EM or WLST. In a rare situation, this error can also happen if the actual keystore type is ORACLE_WALLET and the keystore type specified in JPS configuration file is PKCS12.

WSM-00057
The certificate, {0}, is not retrieved.{4}The location of the key store being used is "{1}" and its type is "{2}". The following aliases are found in the keystore:- {3}

Category:
Configuration

Cause:
Failure occurred while retrieving certificate from store.

Action:
Verify keystore location configuration property as well as make sure that the requested certificate is present.

WSM-00058
The key type {0} is not supported.

Category:
Configuration

Cause:
The private key algorithm that was used is unsupported.

Action:
Ensure that the private key follows the RSA algorithm.

WSM-00059
Signature method algorithms are mismatched. Expected : {0}, Actual : {1}.

Category:
Security

Cause:
Expected and actual values of signature method algorithms did not match.

Action:
Check the policy and WS-Security Policy 1.1 specification for valid values.

WSM-00060
Error validating timestamp.

Category:
Security

Cause:
Timestamp is expired.

Action:
Check the timestamp. Check the allowed clockskew and message expiration time.

WSM-00061
Signature digest verification failure. The system property xml.debug.verify should be enabled for the details about the digest calculations during verification phase (note xml.debug.verify slows down the signature verification for very large messages). Caused by:-{0}

Category:
Security

Cause:
Digest verification failed possibly due to corrupted digest, or a message that was tampered with.

Action:
Recompute the digest and send the message again.

WSM-00062
The path to the certificate used for the signature is invalid.

Category:
Security

Cause:
The intermediate and root certificates of the signing certificate were not present in the keystore at the verifying end.

Action:
Make sure that the entire certificate chain is available in the keystore for verification.

WSM-00063
The version of SAML is incorrect. Expected : {0}, Actual : {1}.

Category:
Security

Cause:
SAML version in the SAML assertion did not match the expected version.

Action:
Check to see that the major version and minor version of the assertion are according to policy.

WSM-00064
SAML subject confirmation mismatch. Expected : {0}, Actual : {1}.

Category:
Security

Cause:
Subject confirmation method in SAML assertion did not match the policy requirements.

Action:
Check to see that the confirmation method for all the SAML assertions is sender-vouches.

WSM-00065
Error sending request over SSL.

Category:
Other

Cause:
Failure in creating SSL request possibly due to invalid configuration of Credential Store FrameWork (CSF).

Action:
Check the JPS configuration for CSF.

WSM-00066
The matching certificate for the given Subject Key Identifier (SKI) cannot be found.

Category:
Security

Cause:
None

Action:
None

WSM-00067
None SOAP message parts can be encrypted.

Category:
Security

Cause:
The elements to be encrypted in the policy were selected to be either of soap Envelope/Body/Header.

Action:
The core soap nodes cannot be encrypted according to WS-Security 1.0 specification.

WSM-00068
The security token is missing.

Category:
Security

Cause:
Security token was expected but was not found.

Action:
Security token is missing. Resend request with valid Security token.

WSM-00069
The security header is missing in request. Ensure that there is a valid security policy attached at the client side, and the policy is enabled.

Category:
Security

Cause:
Security header was expected but was not found.

Action:
Security header is missing. It could be that client side policy has not been applied. Resend request with appropriate Security header.

WSM-00070
The nonce cannot be validated.

Category:
Security

Cause:
Failure occurred while performing nonce Validation.

Action:
This may be due to a repeated value of nonce. Resend the request with a valid nonce.

WSM-00071
Error validating the wsu:Created attribute.

Category:
Security

Cause:
Failure occurred while doing Created(Timestamp) validation.

Action:
Resend the request with a valid timestamp, and or within the expiration limits.

WSM-00072
An encryption algorithm suite policy compliance failure occurred, expected algorithm: {0}, actual algorithm: {1}

Category:
Security

Cause:
Failure occurred in encryption algorithms policy compliance check, expected algorithm: {0}, actual algorithm: {1}

Action:
Check the encryption algorithm requirements of the policy and resend the message with appropriate value of algorithm suite.

WSM-00073
The mechanism {0} used in the authentication header is not supported.

Category:
Configuration

Cause:
The value of mechanism attribute used was not supported.

Action:
Change the policy to point to valid value of mechanism(basic), and retry the operation.

WSM-00074
The authorization header {0} is not correctly encoded using the Base64 encoding.

Category:
Security

Cause:
The authorization header was not encoded according to Base64 requirements.

Action:
Encode the header with Base64(username:realm:password) format and resend the request.

WSM-00075
The realm property is not configured in the policy.

Category:
Configuration

Cause:
The realm property was not configured in the policy.

Action:
Configure appropriate value of realm inside the policy.

WSM-00076
The user name is missing from the encoded authorization header.

Category:
Security

Cause:
The Authorization header did not contain a properly encoded username, or username was null.

Action:
Encode the header with Base64(username:realm:password) format and resend the request.

WSM-00077
The password is missing from the encoded authorization header.

Category:
Security

Cause:
The Authorization header did not contain password encoded properly, or password was null.

Action:
Encode the header with Base64(username:realm:password) format and resend the request.

WSM-00078
The configuration of the credentials in the policy is incorrect.

Category:
Configuration

Cause:
Credential configuration in the policy was incorrect.

Action:
Configure policy with valid Credential Store Framework (CSF) key, or username/password properties.

WSM-00079
The <BinarySecurityToken> element is missing.

Category:
Security

Cause:
<BinarySecurityToken> was not found.

Action:
For reference mechanisms that are configured with value direct, send the certificate inside <BinarySecurityToken> element.

WSM-00080
STR Dereferencing Transform not found

Category:
Security

Cause:
STR Dereferencing Transform was not found.

Action:
For reference mechanisms that are configured with value SKI, the Transforms section should contain the STR Dereferencing Transform.

WSM-00081
The X.509 certificate is not signed.

Category:
Security

Cause:
The X509 token used was not signed according to requirements of certificate authentication scenario.

Action:
Sign the X509 token (depending upon the reference mechanism used) for certificate authentication.

WSM-00082
The roles and/or attributes of the user profile cannot be retrieved.

Category:
Security

Cause:
No information could be obtained regarding the user roles or attributes.

Action:
Try resending the request for another user.

WSM-00083
Error computing the digest for this reference.

Category:
Security

Cause:
Digest computation for the <Reference> failed.

Action:
Check log file for possible cause.

WSM-00084
Error computing <SignatureValue> for this signature block.

Category:
Security

Cause:
Signature value computation for the signature block failed.

Action:
Check log file for possible cause.

WSM-00085
The certificates cannot be retrieved from the keystore.

Category:
Security

Cause:
Failure occurred while trying to retrieve certificate from keystore.

Action:
Use a valid alias for the certificate and retry the operation.

WSM-00086
Error initializing nonce cache.

Category:
Security

Cause:
Failure occurred while initializing iAS Cache.

Action:
Check log file for possible cause.

WSM-00087
Either {0} property or the oracle.j2ee.home system property is not set.

Category:
Security

Cause:
The cache configuration file for iAS cache was not found.

Action:
Set the system property oracle.j2ee.home or javacache.config.home system property to the path of the configuration file javacache.xml.

WSM-00088
The ObSSOCookie is missing.

Category:
Security

Cause:
The OAM security token was not found.

Action:
Resend the request by embedding the ObSSOCookie token inside a <BinarySecurityToken> element.

WSM-00089
The attachments security transform is incorrect. Expected : {0}, Actual : {1}.

Category:
Security

Cause:
The attachment security transform used was incorrect.

Action:
Refer to the recipient's policy for information about which SwA Security Transform is to be used.

WSM-00090
The signature for the attachment is non-compliant.

Category:
Security

Cause:
The attachment signature was not compliant.

Action:
Refer to the recipient's policy for information about which SwA Security Transform is to be used.

WSM-00091
The encryption of the attachment is non-compliant.

Category:
Security

Cause:
The attachment encryption was not compliant.

Action:
Refer to the recipient's policy for information about which SwA Security Transform is to be used.

WSM-00092
The <EncryptedKey> element is missing in the request. Ensure that there is a message protection policy attached at the client side.

Category:
Security

Cause:
No <EncryptedKey> elements were found in the request.

Action:
Refer to the WS-Security 1.0 and 1.0 specifications for the semantics.

WSM-00093
The <saml:Assertion> element is missing in the security header. Ensure that there is a SAML token policy attached at the client side. Tokens found in the security header are:- {0}.

Category:
Security

Cause:
No SAML assertions were found inside the security Header.

Action:
Resend the message with at least one SAML assertion in the header.

WSM-00094
The negotiated cipher suite does not meet policy requirements. Expected : {0}, Actual : {1}.

Category:
Security

Cause:
The negotiated cipher suite did not meet policy requirements.

Action:
Check the recipient's policy for the permitted values of the cipher suite.

WSM-00095
There is more than one assertion assigned to the same category {0} in the security policy.

Category:
Configuration

Cause:
Two or more assertions assigned to the same category were used.

Action:
Ensure that assertions inside a security policy belong to different categories.

WSM-00096
The order of the assertions is incorrect.

Category:
Configuration

Cause:
Assertion order does not match the requirements of policy.

Action:
Use the following order for client side policy : authentication -> msgprotection or authentication -> authorization and following for server side security policy msg-protection -> authentication or msg-protection -> authentication -> authorization.

WSM-00097
HTTP basic authentication header is missing.

Category:
Security

Cause:
HTTP basic authentication header was missing.

Action:
Client must provide the HTTP basic authentication header.

WSM-00098
User realm {0} is either null or is a mismatch with service realm {1}.

Category:
Security

Cause:
User realm was either null or was a mismatch with service realm.

Action:
Make sure user realm sent from client matches with the service realm.

WSM-00099
Username, password, or both are missing from the HTTP authentication header.

Category:
Security

Cause:
Username, password, or both were missing from HTTP authentication header.

Action:
Make sure the HTTP request header contains the username/password token.

WSM-00100
Found more than one keystore files {0} in application classpath. By default the first keystore is used. Make sure the desired keystore is being used by clearing others from the classpath.

Category:
Security

Cause:
Found more than one keystore file in application classpath. By default, the first keystore is used.

Action:
To ensure the desired keystore is being used, remove other keystores from the classpath, if possible.

WSM-00101
The specified keystore file {0} cannot be found; it either does not exist or its path is not included in the application classpath.

Category:
Security

Cause:
Keystore file did not exist or its path was either incorrect or not included in the application classpath.

Action:
Verify the keystore file does exist and its path is included in the application classpath.

WSM-00102
The specified user/subject does not belong to any role in system ID store.

Category:
Security

Cause:
The subject/user did not belong to any defined role in system ID store.

Action:
Verify and make sure that the specified user belongs to one or more roles.

WSM-00103
The policy is configured incorrectly without specifying roles, or denyAll or permitAll elements.

Category:
Security

Cause:
The policy was incorrectly configured with no roles and no denyAll/permitAll elements.

Action:
Correct the policy by configuring it with a denyAll element, a permitAll element, or at least one role.

WSM-00104
The specified JPS context {0} cannot be found in system-level JPS configuration file.

Category:
Security

Cause:
The JPS context could not be found in system level JPS configuration.

Action:
Verify system level JPS configuration file to ensure that it contains the context.

WSM-00105
Credential Store service instance is missing. Either the Oracle WSM JPS context being used for the keystore does not contain a reference to the Credential Store service instance, or the reference is not valid. The Credential Store service instance needs to be declared at the same level (system or application) as the keystore service instance. Therefore, if an application-level keystore is being used, a Credential Store Framework (CSF) store must also be declared at the application level.

Category:
Security

Cause:
No Credential Store (CSF) was found at the level where keystore was used.

Action:
Verify that the WSM JPS context is configured correctly. The error indicates that either the WSM JPS context which is being used for keystore does not contain reference to the Credential Store service instance, or the reference is not valid. The Credential Store service instance needs to be declared at the same level (system or application) as the keystore service instance. Therefore, if an application level keystore is being used, a CSF store must also be declared at the the application level.

WSM-00106
Assertion assigned to a non-security category {0} cannot be added to policy assigned to a security category.

Category:
Security

Cause:
Assertion belonging to non-security categories could not be added to policies belonging to security category.

Action:
Ensure that assertions in security policy also belongs to security category.

WSM-00107
Assertion belonging to {0} category is not valid for generic policy. Only assertion of type security/logging can be added to a generic policy (policy applicable to clients and servers). Check the assertions added to the generic policy.

Category:
Security

Cause:
Invalid assertions were found in generic policy.

Action:
Only assertion of type security/logging can be added to a generic policy (policy applicable to clients and servers). Recheck the assertions added to the generic policy.

WSM-00108
If password type is set to digest, addNonce and addCreated should be true.

Category:
Security

Cause:
UserNameToken Assertion had Passwordtype as digest but addNonce or addCreated was false.

Action:
In case of passwordtype as digest, addNonce and addCreated both should be true. Recheck the assertion.

WSM-00109
Algorithm suite is not supported, only TripleDes is supported for Kerberos assertion.

Category:
Security

Cause:
Kerberos Assertion had algorithm-suite other than TripleDES.

Action:
Only TripleDES algorithm is supported in case of Kerberos, so set algorithm-suite as TripleDes.

WSM-00110
Basic192 and *RSA15 algorithm-suites are not supported for SSL. Change the algorithm suite to one that is supported.

Category:
Security

Cause:
Basic192 or RSA algorithm-suite was used for SSL.

Action:
Use other supported Algorithm-suite for SSL except Basic192 and RSA algorithms.

WSM-00111
Keystore is not properly configured. Check your keystore configurations.

Category:
Security

Cause:
Keystore was not properly configured.

Action:
Check the keystore configuration, and try again.

WSM-00112
Missing keystore service instance reference in Oracle WSM JPS context.

Category:
Security

Cause:
Keystore Service instance reference was not found in WSM JPS Context.

Action:
Add the keystore service instance reference to WSM JPS Context, and try again.

WSM-00113
Unsupported configuration value for Client Credential Configuration location.

Category:
Security

Cause:
An unsupported configuration value of Client Credential location configuration was provided.

Action:
Refer to the documentation for valid values and add the proper configuration value for Client Credential Configuration Location, and try again.

WSM-00114
No matching SSL cipher suite is found for algorithm suite value, specified in the Policy.

Category:
Security

Cause:
No matching SSL cipher suite was found for algorithm suite value, specified in WS Policy.

Action:
Set algorithm suite of Web Service policy to a value that has matching SSL cipher suite.

WSM-00115
JSSE System Property for SSL cipher suite is either not set or does not match algorithm suite value specified in WS Policy.

Category:
Security

Cause:
JSSE System Property for SSL cipher suite was either not set or did not match algorithm suite value specified in WS Policy.

Action:
Set JSSE System Property (https.cipherSuites) to a value that matches algorithm suite as specified in WS Policy.

WSM-00116
Error retrieving SOAP body from SOAP message.

Category:
Security

Cause:
An error ocurred while retrieving SOAPBody from SOAPMessage. Either the SOAPMessage was not proper or had been tampered with.

Action:
Check whether the SOAPMessage is according to the Specifications and try again.

WSM-00117
Error occurred while transforming the security header.

Category:
Security

Cause:
TransformerException occurred while transforming the WssHeader to String. The SOAPMessage might not have been proper or it did not conform to the specifications.

Action:
Check the SOAPMessage and try again.

WSM-00118
OAM token can be inserted only on hosted clients where authenticated subject has been established.

Category:
Security

Cause:
Insertion of an OAM token tried from a non-hosted client where Authenticated Subject is not established.

Action:
Try to add OAM token from a hosted client as only the hosted clients can insert the OAM token extracting it from Authenticated Subject

WSM-00119
Either authorization header or requireTLS must be present.

Category:
Security

Cause:
The security policy attached did not have either auth Header or requireTLS set to true.

Action:
Change the policy to have either auth Header or requireTLS to be true.

WSM-00120
Cannot compute endorsing signature as no message signature is present.

Category:
Security

Cause:
The security policy did not sign anything from the message, so no signature was there. Endorsing Signature could not be computed as the signature which it was trying to endorse was not present.

Action:
Change the policy to Sign at least something in the message.

WSM-00121
Only the attachments are to be signed/encrypted and they are not present.

Category:
Security

Cause:
Only the attachments were to be signed/encrypted and they were not present.

Action:
Retry after putting attachments in the SOAP Message.

WSM-00122
Valid timestamp is not present in the message. It is missing the Created time.

Category:
Security

Cause:
Valid timestamp was not present in the message. It was missing the Created time.

Action:
Ensure the timestamp element conforms to the specifications.

WSM-00123
Timestamp of the message is in future.

Category:
Security

Cause:
The message had Created timestamp of a time in future so it failed Future message validation.

Action:
Ensure freshness of the message and check WSM configuration system for the configured value of clock skew.

WSM-00124
Timestamp of the message is in past.

Category:
Security

Cause:
The message was older than the permissible time limit so it failed Past message validation.

Action:
Ensure freshness of the Message and check the WSM configuration system for the configured values of clock skew and expire time.

WSM-00125
Password digest validation failed.

Category:
Security

Cause:
The password digest in the message was not correct so it failed the digest validation.

Action:
Retry after ensuring password digest is proper.

WSM-00126
Subject does not contain JPS user.

Category:
Security

Cause:
The subject mentioned did not have the JPS User.

Action:
Retry after ensuring JPS user in the subject.

WSM-00127
User not in identity store.

Category:
Security

Cause:
The user mentioned was not present in the identity store.

Action:
Retry after ensuring that user is present in the identity Store.

WSM-00128
Keystore instance is null.

Category:
Security

Cause:
Could not obtain keystore instance. Either the keystore instance type was wrong or the keystore configuration was wrong.

Action:
Check JPS configuration settings. Use correct keystore instance type.

WSM-00129
Unsupported SAML token provided : {0}.

Category:
Security

Cause:
An unsupported SAML token confirmation method was provided.

Action:
Provide a supported SAML token confirmation method and retry the operation.

WSM-00130
SAML assertion subject is missing.

Category:
Security

Cause:
The SAML assertion subject name was not specified.

Action:
Provide the SAML assertion subject and retry the operation.

WSM-00131
Unsupported data encryption algorithm: {0}.

Category:
Security

Cause:
An unsupported data encryption algorithm was provided.

Action:
Consult the documentation for the supported encryption algorithms and retry the operation.

WSM-00132
Invalid JPS configuration.

Category:
Security

Cause:
An invalid JPS configuration was provided.

Action:
Make sure that the JPS configuration is valid.

WSM-00133
Unsupported MessageContext type {0}.

Category:
Configuration

Cause:
Unsupported MessageContext type was provided.

Action:
Correct the MessageContext type and retry the operation.

WSM-00134
The signature key, {0}, is not retrieved due to exception {1}.

Category:
Security

Cause:
Error occurred while obtaining the signature key from store.

Action:
Check JPS configuration settings. Make sure that the key password , keystore password, and key alias are valid.

WSM-00135
The encryption key, {0}, is not retrieved due to exception {1}.

Category:
Security

Cause:
Error occurred while obtaining encryption key from store.

Action:
Check JPS configuration settings. Use correct key password, keystore password, and key alias.

WSM-00136
The signature certificate, {0}, is not retrieved due to exception {1}.

Category:
Security

Cause:
Failure occurred while retrieving the signature certificate from store.

Action:
Check JPS configuration settings for keystore location and make sure that the requested certificate is present.

WSM-00137
The encryption certificate, {0}, is not retrieved due to exception {1}.

Category:
Security

Cause:
Failure occurred while retrieving the encryption certificate from store.

Action:
Check JPS configuration settings for keystore location and make sure that the requested certificate is present.

WSM-00138
The path to the certificate is invalid. Validation failed for the certificate {0}

Category:
Security

Cause:
The intermediate and root certificates of the certificate were not present in the keystore during verification.

Action:
Make sure that the entire certificate chain is available in the keystore for verification.

WSM-00139
The scenario category {0} is not supported.

Category:
Security

Cause:
The scenario category is not supported.

Action:
Consult the Oracle documentation for supported categories.

WSM-00140
Invalid execution stage {0} resulting in system internal error.

Category:
Security

Cause:
System encountered an invalid execution stage.

Action:
Retry the operation, If problem persists contact Oracle Support Services.

WSM-00141
Error retrieving SOAP header from SOAP message.

Category:
Security

Cause:
An error occurred while retrieving the header from the SOAP Message. The SOAP message was invalid or was tampered with.

Action:
Make sure that the SOAP message is valid according to the specifications and retry the operation.

WSM-00142
Assertion belonging to {0} category is not valid for Component policy

Category:
Security

Cause:
Assertion belonging to authentication or message protection category was found in Component policy and it is invalid.

Action:
Modify the policy to correct the problem and retry the operation.

WSM-00143
Failure creating Java Keystore instance for type {0}.

Category:
Configuration

Cause:
Either the keystore type provided is not supported or there is no implementation provider for Java keystore.

Action:
Consult the Oracle documentation for supported Keystore types and make sure the implementation provider for Java Keystore is available.

WSM-00144
Failure retrieving Keystore aliases.

Category:
Configuration

Cause:
Keystore may have not been initialized.

Action:
Check the log file for possible causes and retry the operation.

WSM-00145
Keystore location or path can not be null or empty; it must be configured through the domain level configuration or policy configuration override.

Category:
Configuration

Cause:
Keystore location/path was either missing, set to be null, or empty.

Action:
Make sure that Keystore location is configured properly in the domain level configuration or through policy configuration override.

WSM-00146
Keystore type {0} defined using keystore.type property in the domain level configuration or through policy configuration override is not supported.

Category:
Configuration

Cause:
Invalid or unsupported keystore.type property value was found.

Action:
Consult the oracle documentation to ensure that a valid keystore.type is configured either through the domain level configuration or using policy configuration override.

WSM-00147
JPS context property is no longer supported in policy configuration

Category:
Configuration

Cause:
Unsupported JPS context property value was found.

Action:
Remove JPS context property from the configuration file.

WSM-00148
Security policy cannot be applied to streamed attachments. Streaming should be turned off if there are any security policies for attachments.

Category:
Configuration

Cause:
Security policy cannot be applied to streamed attachments.

Action:
Make sure streaming is off if security policies are being used for attachments.

WSM-00149
SAML assertion is missing.

Category:
Security

Cause:
Failed to locate SAML assertion with ID {0}.

Action:
Make sure that a valid SAML asssertion exists.

WSM-00150
Processed header list fetched from InterceptorContext is null, agentFunction:{0}, listType:{1}.

Category:
Security

Cause:
Processed header list fetched from InterceptorContext is null.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-00151
Role class {0} specified in the policy is either invalid or is not available in the classpath. Exception thrown : {1}.

Category:
Configuration

Cause:
Class name required for retrieving principal/role from subject is either invalid or class not present in the classpath

Action:
Specify a valid class name in the policy and ensure that the instances of the class specified are associated with the subject created.

WSM-00152
Callback {0} is not supported by Oracle WSM callback handler.

Category:
Security

Cause:
Callback specified is not supported by Oracle WSM callback handler.

Action:
Specify a valid callback class that Oracle WSM callback handler can support.

WSM-00153
Error retrieving Weblogic Server subject from JPS subject using SubjectSecurityUtil API

Category:
Security

Cause:
A failure occurred while converting JPS subject to Weblogic Server subject.

Action:
Check log file for possible cause.

WSM-00154
The empty or all-spaces value set explicitly for property {0} is detected and it is not valid value.

Category:
Security

Cause:
The property value was probably set unintentionally to empty or all-spaces through policy configuration override or JPS configuration.

Action:
Make sure that the value provided either through policy configuration override, policy binding, or JPS configuration is not empty or all spaces.

WSM-00155
Error retrieving Oracle WSM security policies.

Category:
Security

Cause:
A failure occurred while retrieving Oracle WSM security policies.

Action:
Check log file for possible cause.

WSM-00156
Invalid binary security token.

Category:
Security

Cause:
Binary security token in the header and the certificate used for endorsing signature did not match.

Action:
Make sure a valid binary security token is being passed.

WSM-00157
Recipient key alias not configured and signer certificate was not available because no part of the request was signed.

Category:
Security

Cause:
Recipient key alias not configured and signer's certificate was not available because no part of request was signed.

Action:
Set recipient key alias in service policy or sign part of the request.

WSM-00158
KerberosLoginModule class is not available in the classpath

Category:
Security

Cause:
The class for the Kerberos login module was not available in the classpath.

Action:
Make sure that the KerberosLoginModule class is included in the classpath, and configure the class name properly in WSM configuration system.

WSM-00159
TextCallbackHandler class is not available in the classpath

Category:
Security

Cause:
The class for the Text callback handler was not available in the classpath.

Action:
Make sure that the TextCallbackHandler class is included in the classpath, and configure the class name properly in WSM configuration system.

WSM-00160
The SSL policy must contain a requireTLS element.

Category:
Security

Cause:
The security policy attached did not have requireTLS set to true.

Action:
Change the policy to have requireTLS as true.

WSM-00161
Client encryption public certificate is not configured for Async web service client

Category:
Security

Cause:
Client encryption public certificate is not configured for async web service client with message protection.

Action:
Make sure that client public certificate is configured in client keystore, or provided through client config override for Async web service client that uses message protection

WSM-00162
Invalid recipient cert type: {0} may have been provided through override; It should be either a X509Certificate object or Base64 encoded value in String format.

Category:
Configuration

Cause:
Invalid recipient cert type may have been provided through override; It should be either a X509Certificate object or Base64 encoded value in String format.

Action:
Verify that only X509Certificate object, or Base64 encoded String value are provided in Policy, descriptor file or through program.

WSM-00163
Failure in getting recipient certificate using recipient key alias {0}

Category:
Configuration

Cause:
The recipient key alias might not be valid

Action:
Check to see if there is such certificate in keystore corresponding to the recipient key alias provided.

WSM-00164
Cannot obtain a valid recipient cert for client message sending

Category:
Configuration

Cause:
Encountered error while obtaining recipient certificate for sending request.

Action:
Must provide valid recipient certificate, or recipient alias for client to send request with message protection.

WSM-00165
Creating recipient certificate from base64 encoded string: {0} failed.

Category:
Configuration

Cause:
Encountered error while creating recipient certificate from base64 encoded string.

Action:
Must provide valid certificate in valid base64 encoded string.

WSM-00166
Extract certificate from saved ReplyTo header failed.

Category:
Configuration

Cause:
X509Certificate within ReplyTo header element might be invalid.

Action:
Ensure that cert. insertion, ReplyTo header serialization/deserializaton to JMS queue are all working properly.

WSM-00167
Actual Hostname {0} and Hostname retrieved from Certificate {1} do not match

Category:
Security

Cause:
HostName verification of certificate retrieved from WSDL failed

Action:
Either ensure that the Subject Dn matches the Hostname of the Service or disable the HostName Verification check

WSM-00168
Unable to extract X509Certificate from WSDL Definition Object as WSDL definition Object is unavailable

Category:
Security

Cause:
WSDL definition required for extraction of X509Certificate not available

Action:
Ensure that WSDL Definition Object is available from the MessageContext

WSM-00169
Error decrypting the request message.

Category:
Security

Cause:
The request message could not be decrypted using the key specified for decryption.

Action:
Ensure that the key used for decryption is same as the one used for encryption.

WSM-00170
There are no assertions available under the ExactlyOne policy operator.

Category:
Security

Cause:
There are no assertions under ExactlyOne policy operator.

Action:
Ensure that one or more security assertions are kept under ExactlyOne policy operator.

WSM-00171
A client policy contains an ExactlyOne policy operator.

Category:
Security

Cause:
A client policy contained an ExactlyOne policy operator.

Action:
Remove the ExactlyOne policy operator or switch to a service binding.

WSM-00172
A generic policy contains an ExactlyOne policy operator.

Category:
Security

Cause:
A generic policy contained an ExactlyOne policy operator.

Action:
Remove the ExactlyOne policy operator or switch to a service binding.

WSM-00173
A policy contains more than one ExactlyOne policy operator.

Category:
Security

Cause:
A policy contained more than one ExactlyOne policy operator.

Action:
Remove the additional ExactlyOne policy operators.

WSM-00174
A policy contains a nested ExactlyOne policy operator.

Category:
Security

Cause:
A policy contained a nested ExactlyOne policy operator.

Action:
Remove the nested ExactlyOne policy operators.

WSM-00175
Recipient Certificate for async callback client is not found under the ReplyTo element in async callback client message context

Category:
Configuration

Cause:
Recipient cert. for async callback client is not available from message context.

Action:
Ensure that original async client has public encryption certificate configured and is inserted into the ReplyTo header or the original async request. Also ensure that the original ReplyTo header along with client encryption certification is preserved and restored to the callback client message context.

WSM-00176
The mapped long name(s) for property {0} is null, the property might not be available for client programmatic override. Make sure it is indeed the intention, otherwise, add a mapping to map ConfigOverrideMapping.

Category:
Configuration

Cause:
The config override property does not have a corresponding long name mapping

Action:
Make sure this is indeed intended, otherwise, add a mapping to the ConfigOverrideMapping.

WSM-00177
The CSF key provided by the user is not present in the credential store. So using the default key is being used.

Category:
Security

Cause:
The CSF key provided by the user is not present in the credential store

Action:
Provide a valid key. Till then the default key will be used.

WSM-00178
Public key not found for SAML signature verification.

Category:
Configuration

Cause:
Public key not found for SAML signature verification

Action:
Ensure that public key is present in Security header which is reqruied For SAML signature verification

WSM-00179
SAML assertion issuer name is invalid.

Category:
Security

Cause:
SAML assertion issuer name is invalid.

Action:
Check to see that the overridden SAML trused issuers has SAML assertion issuer name.

WSM-00180
The trust version {0} is not supported for policy advertisement, hence ignored. The default trust version {1} is advertised.

Category:
Configuration

Cause:
The trust version specified in the policy is not supported.

Action:
Modify the policy with a supported trust version.

WSM-00181
A policy issued-token attributes require-internal-reference and require-external-reference both are false, one of them has to be true.

Category:
Configuration

Cause:
A policy issued-token attribute require-internal-reference and require-external-reference can not both be false.

Action:
At least one of the attribute require-internal-reference and require-external-reference must be set to true

WSM-00182
A policy request-security-token-template element attribute token-type has an unsupported value: {0}

Category:
Configuration

Cause:
A policy request-security-token-template element contains a token-type that is not supported.

Action:
Check documentation for supported token-type

WSM-00183
A policy request-security-token-template element attribute algorithm-suite has a value: {0} which does not match to that of msg-security: {1}, change it to match {1}.

Category:
Configuration

Cause:
A policy request-security-token-template element contains an algorithm-suite value that does not match to that of msg-security.

Action:
Change the algorithm-suite attribute value to match exactly the one in msg-security

WSM-00184
An attribute trust-version has an unsupported version: {0}

Category:
Configuration

Cause:
A policy contains an unsupported WS-TRUST version.

Action:
Check documentation for supported WS-TRUST version

WSM-00185
Attribute require-client-entropy and require-server-entropy can not both be set to false, at lease one of them must be set to true.

Category:
Configuration

Cause:
A policy can not have both require-client-entropy and require-server-entropy attributes set to false.

Action:
At lease set one of them to true

WSM-00186
A policy request-security-token-template key-type attribute is expected to be: {0}, but got: {1}

Category:
Configuration

Cause:
A policy request-security-token-template key-type attribute value is not set to the expected Bearer.

Action:
Set the attribute value to the expected

WSM-00187
A policy request-security-token-template key-type attribute is expected to be: {0}, but got: {1}

Category:
Configuration

Cause:
A Bearer policy request-security-token-template key-type attribute value is not set to the expected Symmetric or Public.

Action:
Set the attribute value to one of the expeted value Symmetric or Public

WSM-00188
STS Trust Config policy attribute port-uri has invalid value "{0}", it must be not null, not empty and in the format of http(s)://host:port/sts-service

Category:
Configuration

Cause:
STS trust config attribute port-uri is either null, empty or not in the format of "http(s)://host:port/sts-service-name".

Action:
Provide valid attribute value which is in the format of "http(s)://host:port/sts-service"

WSM-00189
STS Trust Config policy attribute port-endpoint has invalid value "{0}", it must be not empty and in the format of target-namespace#wsdl.endpoint(service-name/port-name)

Category:
Configuration

Cause:
STS trust config attribute port-endpoint is either empty or not in the format of "target-namespace#wsdl.endpoint(service-name/port-name)".

Action:
Provide valid attribute value which is in the format of "target-namespace#wsdl.endpoint(service-name/port-name)"

WSM-00190
STS Trust Config policy attribute policy-reference-uri can not have empty value.

Category:
Configuration

Cause:
The value of STS trust config attribute policy-reference-uri is empty or not in the URI format

Action:
Specify value for attribute policy-reference-uri

WSM-00191
STS Trust Config policy attribute sts-keystore-recipient-alias can not have null or empty value.

Category:
Configuration

Cause:
The value of STS trust config attribute sts-keystore-recipient-alias is null or empty

Action:
Specify a non null or empty value for attribute sts-keystore-recipient-alias

WSM-00192
Kerberos name identifier format is not supported for SAML 1.1 token.

Category:
Security

Cause:
Kerberos name identifier format is not supported for SAML 1.1 token.

Action:
Kerberos name identifier format is only for SAML 2.0 token, use other name identifier formats.

WSM-00193
Security policy contains NULL or empty value for signed-element local name or namespace.

Category:
Security

Cause:
Security policy contains NULL or empty value for signed-element local name or namespace.

Action:
Signed-element local name or namespace must not be null or empty.

WSM-00194
Security policy contains NULL or empty value for signed-part header namespace.

Category:
Security

Cause:
Security policy contains NULL or empty value for signed-part header namespace.

Action:
Signed-part header namespace must not be null or empty.

WSM-00195
Security context for derived key unknown (cannot determine the base symmetric key).

Category:
Security

Cause:
Security context for derived key unknown (cannot determine the base symmetric key).

Action:
DerivedKeyToken should include SecurityReferenceToken (can only be empty in responses where the message context includes the base key).

WSM-00196
Unable to resolve base key referenced in DerivedKeyToken.

Category:
Security

Cause:
Unable to resolve base key referenced in DerivedKeyToken.

Action:
Ensure the SecurityTokenReference in the DerivedKeyToken specifies a valid base key within the security context.

WSM-00197
Unsupported SecurityTokenReference type for DerivedKeyToken : {0}.

Category:
Security

Cause:
Unsupported SecurityTokenReference type for DerivedKeyToken.

Action:
Ensure the SecurityTokenReference in the DerivedKeyToken is one of the supported types.

WSM-00198
Unable to resolve EncryptedKey that matches EncryptedKeySHA1 in KeyInfo.

Category:
Security

Cause:
Unable to resolve EncryptedKey that matches EncryptedKeySHA1 in KeyInfo.

Action:
The value of the EncryptedKeySHA1 should match an encrypted key in the security context.

WSM-00199
Unsupported key identifier type "{0}" in security token reference.

Category:
Security

Cause:
Unsupported key identifier type in security token reference.

Action:
Use only of the supported key idetifier types in the security token.

WSM-00200
Exception encountered while checking compliance; returning false.

Category:
Security

Cause:
Exception encountered while checking compliance; returning false.

Action:
Check log for exception details.

WSM-00201
There are no <EncryptedKey> elements in the request.

Category:
Security

Cause:
There are no <EncryptedKey> elements in the request.

Action:
The request should have an <EncryptedKey> element.

WSM-00202
Proof key type is invalid, valid values are null, public, symmetric.

Category:
Configuration

Cause:
The value of ketype is invalid for SAML Issued Token Policy , valid values are null (no proof key), public, symmetric

Action:
Specify valid value for keytype based on the policy

WSM-00203
Invalid OPSS Trust Service

Category:
Configuration

Cause:
OPSS TrustService is empty or null

Action:
Configure Trust Service in OPSS

WSM-00204
Invalid issued token from trust token exchange

Category:
Requests/Responses

Cause:
Issued token is null

Action:
Check Logs and correct any errors during issuance

WSM-00205
Proof key type is invalid, valid value is bearer

Category:
Configuration

Cause:
The value of ketype is invalid for SAML Bearer Issued Token Policy , valid value is bearer

Action:
Specify bearer as the key type for this policy

WSM-00206
Requester credentials for authenticating to STS are invalid

Category:
Configuration

Cause:
Requester Credentials required for autenticating to STS are missing

Action:
Configure sts.auth.user.csf.key or sts.auth.x509.csf.key in issued token policy

WSM-00207
Asymmetric proof key is invalid

Category:
Configuration

Cause:
Assymetric proof key is invalid

Action:
Configure sts.auth.x509.csf.key in issued token policy

WSM-00208
STS On behalf of user is invalid

Category:
Configuration

Cause:
STS On behalf of user is invalid

Action:
Configure sts.auth.on.behalf.of.csf.key in issued token policy

WSM-00209
Permission{0} required to switch the identity not granted to the resource. {1}

Category:
Security

Cause:
Permission required to switch the identity not granted

Action:
Grant Permission for identity switching to the codesource.

WSM-00210
Client is unable to find actual webservice endpoint to set in appliesTo

Category:
Configuration

Cause:
Client requires appliesTo and unable to find the actual webservice endpoint URL

Action:
Chenck if agent binding ws port ID , service name and port name in log file

WSM-00211
Trust token provider tried creating RequestSecurityToken message and it failed because algorithm use to generate asymmetric key pair was invalid

Category:
Requests/Responses

Cause:
Trust token provider tried creating RequestSecurityToken message and it failed because algoirthm use to generate asymmetric key pair was invalid

Action:
Check the asymmetric key algorithm

WSM-00212
Trust token provider tried creating RequestSecurityToken message and it failed because asymmetric proof key was invalid

Category:
Requests/Responses

Cause:
Trust token provider tried creating RequestSecurityToken message and it failed because assymetic proofk key was invalid

Action:
Check if sts.auth.x509.csf.key is configured correctly in issued token client policy

WSM-00213
Unable to parse SOAP message sent by STS

Category:
Requests/Responses

Cause:
Unable to parse SOAP message sent by STS

Action:
Check if message sent by STS is valid

WSM-00214
Unable to parse RequestSecurityTokenRespnseCollection

Category:
Requests/Responses

Cause:
Unable to parse RequestSecurityTokenResponseCollection

Action:
Check if RequestSecurityTokenResponseCollection message sent by STS is valid

WSM-00215
Unable to parse STSTrustConfig

Category:
Requests/Responses

Cause:
Unable to parse STSTrustConfig

Action:
Check if STSTrustConfig is valid

WSM-00216
Unable to create SOAP RequestSecurityToken message

Category:
Requests/Responses

Cause:
Unable to create SOAP RequestSecurityToken message

Action:
Failure in creating SOAP RequestSecurityToken message, check log files

WSM-00217
STS endpoint URL or WSDL URL (if configured) is invalid

Category:
Requests/Responses

Cause:
STS endpoit URL is invalid

Action:
Check if STS endpoint URL is valid

WSM-00218
Security token returned by STS is null

Category:
Requests/Responses

Cause:
Security token returned by STS is null

Action:
Check if RSTR message sent by STS is valid

WSM-00219
Proof token returned by STS is null

Category:
Requests/Responses

Cause:
Proof token returned by STS is null

Action:
Check if RSTR message sent by STS is valid

WSM-00220
Invalid proof token type, valid values are computedKey and BinarySecret

Category:
Requests/Responses

Cause:
Invalid proof token type, valid values are computedKey and BinarySecret

Action:
Check the proof token type, valid values are computedKey and BinarySecret

WSM-00221
Computed key in RSTR message sent by STS is invalid

Category:
Requests/Responses

Cause:
Computed key in RSTR message sent by STS is invalid

Action:
Check the computed key in RSTR message sent by STS

WSM-00222
Computed key algorithm in RSTR message sent by STS is invalid}

Category:
Requests/Responses

Cause:
Computed key algorithm in RSTR message sent by STS is invalid, valid value is http://docs.oasis-open.org/ws-sx/ws-trust/200512/CK/PSHA1

Action:
Check the computed key in RSTR message sent by STS, valid value is http://docs.oasis-open.org/ws-sx/ws-trust/200512/CK/PSHA1

WSM-00223
Request type is invalid, valid value is issue

Category:
Requests/Responses

Cause:
Request type invalid, valid value is issue

Action:
Check request type in response sent by STS

WSM-00224
User credentials of the user on behalf of whom the token is to be issued is missing

Category:
Requests/Responses

Cause:
User credentials of the user on behalf of whom the token is to be issued is missing

Action:
Check on.behalf.of property in issued token policy. If its set to true then either subject or sts.auth.on.behalf.of.csf-key property needs to be present

WSM-00225
STS On behalf of user password is invalid

Category:
Configuration

Cause:
STS On behalf of user password is invalid

Action:
Configure sts.auth.on.behalf.of.csf.key in issued token policy

WSM-00226
Security policy contains NULL or empty value for encrypted-element local name or namespace.

Category:
Security

Cause:
Security policy contains NULL or empty value for encrypted-element local name or namespace.

Action:
Encrypted-element local name or namespace must not be null or empty.

WSM-00227
Could not resolve key to use for decryption.

Category:
Security

Cause:
Could not resolve key to use for decryption.

Action:
Ensure request contains all the information necessary to succesfully resolve decryption key.

WSM-00228
Oracle system user is missing in identity store

Category:
Configuration

Cause:
Could not find oracle system user .

Action:
Check if OracleSystemUser exists in identity store

WSM-00229
jndi.lookup.csf.key missing in policy-accessor-config

Category:
Configuration

Cause:
Could not find valid jndi.lookup.csf.key in wsm configuration system .

Action:
Check jndi.lookup.csf.key is configured correclty in policy-accessor-config.xml

WSM-00230
Cannot find service information from WSDL {0}

Category:
Requests/Responses

Cause:
Cannot find service information from WSDL

Action:
Check the service information in the WSDL

WSM-00231
Cannot find client compatible policy for STS {0}, port name {1}

Category:
Requests/Responses

Cause:
Cannot find compatible client policy for STS invocation

Action:
Check if policy store has compatible client policy

WSM-00232
Failed to create dynamic STS policy

Category:
Requests/Responses

Cause:
Failed to create dynamic STS policy

Action:
Check exception stack trace for details

WSM-00233
STS WSDL URI {0} is invalid

Category:
Configuration

Cause:
STS trust config attribute wsdl-uri is not in the format of "http(s)://host:port/sts-service?wsdl".

Action:
Provide valid attribute value which is in the format of "http(s)://host:port/sts-service?wsdl

WSM-00234
The <saml:Assertion> element of version {0} is missing in the security header.

Category:
Requests/Responses

Cause:
Saml assertion with specific version e.g. 1.1, or 2.0 etc. is missing. in the received message

Action:
Check exception stack trace for details

WSM-00235
Failed to initialize dispatcher

Category:
Requests/Responses

Cause:
Failed to initialize dispatcher for client to STS communication

Action:
Check exception stack trace for details

WSM-00236
Keystore name property value was not set through the domain level configuration

Category:
Security

Cause:
Keystore name property value was not set through the domain level configuration.

Action:
Make sure that the value is provided for keystore name through the domain level configuration.

WSM-00237
KSS keystore with URI {0} can not be loaded due to {1}.

Category:
Configuration

Cause:
The following KSS keystore-related configuration properties may not be valid:keystore.type, location. Also, check permissions on the keystore.

Action:
Verify the configuration properties mentioned above and retry the operation.

WSM-00238
Unable to read KSS keystore. Grant necessary permission to read KSS keystore with URI {0}

Category:
Configuration

Cause:
KKS keystore may have not been initialized or necessary permissions are not granted.

Action:
Ensure that necessary permission to read KSS keystore is granted.

WSM-00239
KSS trust store can not be loaded, ensure that necessary permissions are granted.

Category:
Configuration

Cause:
KSS trust store can not be loaded, probably necessary permissions are not granted.

Action:
Ensure that necessary permission to read KSS trust store is granted.

WSM-00240
KSS trust store is NULL, ensure that KSS system trust store exist.

Category:
Configuration

Cause:
KSS trust store is NULL, may be it doesn't exists or probably necessary permissions are not granted.

Action:
Ensure that KSS trust store exists in system stripe and permissions are granted.

WSM-00241
Failure retrieving KSS trust store aliases.

Category:
Configuration

Cause:
KSS trust store may have not been initialized.

Action:
Check the log file for possible causes and retry the operation.

WSM-00242
The certificates cannot be retrieved from the trust store.

Category:
Security

Cause:
Failure occurred while trying to retrieve certificate from trust store.

Action:
Use a valid alias for the certificate and retry the operation.

WSM-00243
Unable to read key from KSS keystore. Grant necessary permission to read alias {1} from KSS keystore with URI {0}

Category:
Configuration

Cause:
Unable to read key from KSS keystore. KSS keystore may have not been initialized or necessary permissions are not granted.

Action:
Ensure that alias exists in keystore and necessary permission to read key alias is granted.

WSM-00244
Unable to read certificate from KSS keystore. Grant necessary permission to read certificate alias {1} from KSS keystore with URI {0}

Category:
Configuration

Cause:
Unable to read certificate from KSS keystore. KSS keystore may have not been initialized or necessary permissions are not granted.

Action:
Ensure that alias exists in keystore and necessary permission to read certificate alias is granted.

WSM-00245
Failure retrieving KSS key store aliases.

Category:
Configuration

Cause:
Unable to list alias from KSS key store.

Action:
Check the log file for possible causes and retry the operation.

WSM-00246
Failure retrieving IssuedTokenAssertion from advertised policy.

Category:
Data

Cause:
Possibilly there is a failure in parsing the advertised policy

Action:
Check the log file for possible causes and retry the operation.

WSM-00247
Failed to sign with RSA Key Pair

Category:
Security

Cause:
Failed to sign with RSA Key Pair

Action:
Check exception stack trace for details

WSM-00248
Attesting entity attribute {0} is unsupported.

Category:
Security

Cause:
Unsupported attesting entity attribute is used

Action:
Attesting entity attribute must be DN.

WSM-00249
SAML token DN validation failed for SAML assertion signer DN {0}.

Category:
Security

Cause:
SAML token DN list validation failed.

Action:
Assertion signer DN is not present in trusted DN list, if DN is valid then add it to trusted DNs list.

WSM-00250
Unable to find an implementation class for {0}.

Category:
Security

Cause:
Unable to find an implementation class for 'javax.el.ExpressionFactory'.

Action:
Make sure that the implementation class for 'javax.el.ExpressionFactory' is available in the classpath.

WSM-00251
Failed to create an instance of {0}.

Category:
Security

Cause:
Failed to create an instance of the javax.el.ExpressionFactory implementation class.

Action:
Make sure that the javax.el.ExpressionFactory implementation class can be instantiated.

WSM-00252
Failed to evaluate the constraint expression "{0}" due to the exception: {1}

Category:
Security

Cause:
Failed to evaluate the constraint expression.

Action:
Make sure that the constraint expression is valid. Check exception stack trace for details.

WSM-00253
The constraint expression "{0}" is not valid. The constraint expression should evaluate to the boolean values.

Category:
Security

Cause:
The constraint expression is not valid.

Action:
Make sure that the constraint expression evaluates to the boolean values.

WSM-00254
The message is expired. Check the timestamp element in the message. The current server time is "{0}", incoming message creation time is "{6}", configured agent expiry is {5} seconds, incoming message expiry is {7} seconds, effective message expiry (minimum of agent expiry and incoming message expiry) is {4} seconds, configured clock skew is {3} seconds. The acceptable time range is "{1}" to "{2}". The incoming message is outside the valid range as allowed by clock skew and expiry times.

Category:
Security

Cause:
The incoming message is outside the valid range as allowed by clock skew and expiry times.

Action:
Adjust times on servers/clients. Check the allowed clockskew and message expiration time and configure them as required.

WSM-00256
The property "{0}" is not set. The csf maps that are used to retrieve property are:- "{1}". The properties found in the JPS config are <PropertyName: Value>:- {2}

Category:
Security

Cause:
The property value is null.

Action:
Make sure that the value provided either through policy configuration override, policy binding, or domain level configuration is not null.

WSM-00257
Callback class name "{0}" set for SAML certificate validation not found

Category:
Security

Cause:
Callback class set for SAML certificate validation not found.

Action:
Make sure that callback class name is correct and added in classpath.

WSM-00258
Callback class name "{0}" set for SAML certificate validation is invalid.

Category:
Security

Cause:
Callback class set for SAML certificate validation is not valid.

Action:
Make sure that callback class correctly extends required class.

WSM-00259
SAML certificate validation callback failed. {0}.

Category:
Security

Cause:
Callback class set for SAML certificate validation failed.

Action:
Check the error message for details.

WSM-00260
SAML over SSL certificate validation failed because certificate returned from callback and actual certificate differ. Actual certificate DN={0} and callback cert DN={1}

Category:
Security

Cause:
SAML over SSL certificate validation failed because certificate returned from callback and actual certificate differ.

Action:
Make sure that client certificate sent over SSL and certificate returned from callback are same.

WSM-00261
SAML certificate validation callback failed because certificate returned from callback is NULL.

Category:
Security

Cause:
Callback class set for SAML certificate validation failed because certificate returned from callback is NULL.

Action:
Check callback implementation class for the reason of null certificate.

WSM-00262
SAML assertion with confirmation method {0} is missing inside signature.

Category:
Security

Cause:
SAML assertion is missing inside signature.

Action:
Ensure that SAML assertion has required inside signature.

WSM-00263
Failed to create SAML token as 'anonymous' user principal found in Subject.

Category:
Security

Cause:
Failed to create SAML token as 'anonymous' user principal found in Subject.

Action:
Make sure that the subject is created from a valid user.

WSM-00264
Must Understand check failed for headers: "{0}" in the SOAP message.

Category:
Security

Cause:
Unprocessed 'mustUnderstand' header element in SOAP message.

Action:
Make sure that you have attached security policy at service side.

WSM-00265
The Username token is missing in the security header. Ensure that there is a Username token policy attached on the client side. Tokens found in the security header are :- {0}.

Category:
Security

Cause:
Username token was expected in the security header but was not found.

Action:
Username token is missing. Resend request with valid username token.

WSM-00266
The Kerberos token is missing in the security header.

Category:
Security

Cause:
Kerberos token was expected in the security header but was not found.

Action:
Resend request with valid kerberos token.

WSM-00267
Authentication token specified in the policy for re-authenticate in secure conversation is not supported. Only SAML token is supported currently.

Category:
Configuration

Cause:
Authentication token specified in the policy for re-authenticate in secure conversation is not supported.

Action:
Only SAML token is supported as of now.

WSM-00268
The certificate to be validated is NULL.

Category:
Security

Cause:
The certficate to be validated is null.

Action:
Make sure that the certificate to be validated is not null.

WSM-00269
There is no trusted certificate found in the trust store.

Category:
Security

Cause:
Trust store does not have any trusted certificate.

Action:
Make sure that the required trusted certificates are present in the trust store.

WSM-00270
The issuer "{0}" is not found in the trust store.

Category:
Security

Cause:
The issuer certificate is not present in the trust store.

Action:
Make sure that the issuer certificate is present in the trust store.

WSM-00271
Basic constraints check failed due to the certificate "{0}" is not a CA certificate.

Category:
Security

Cause:
The certificate is not a CA certificate.

Action:
Make sure that the issuer certificate is a CA certificate.

WSM-00272
Basic Constraints check failed for the certificate "{0}", since only an end-entity certificate may follow this certificate in the certification path chain.

Category:
Security

Cause:
Basic Constraints check failed for the issuer certificate.

Action:
Make sure that the issuer certificate is a valid.

WSM-00273
Failed to verify the issuer "{0}".

Category:
Security

Cause:
The issuer certificate verification failed.

Action:
Check error logs for more details.

WSM-00274
The certification path for the certificate "{0}" is NULL.

Category:
Security

Cause:
The certification path is found to be null.

Action:
Check error logs for more details.

WSM-00275
The Identity type "{0}" is not supported.

Category:
Security

Cause:
The Identity type published in the WSDL certificate is not supported.

Action:
Make sure that the identity type published in the WSDL certificate is either X509Certificate or supported one.

WSM-00276
Validation failed for the identity published in the WSDL endpoint "{1}". Caused By: {0}

Category:
Security

Cause:
Validation failed for the Identity published in the WSDL certificate.

Action:
Check error logs for more details.

WSM-00277
Endorsing signature is not found in the message. Ensure that a compatible policy is attached at the client side. The security policy "{1}" is attached to the service. Tokens found in the security header are :- {0}.

Category:
Security

Cause:
Endorsing signature is expected in the message but not found.

Action:
Make sure that the endorsing signature is included in the message.

WSM-00278
Failed to decrypt the encrypted key due to {1}. Ensure that the client is properly configured with the server certificate. Client should be using this certificate:- {0}.

Category:
Security

Cause:
An error occurred while decrypting the encrypted key.

Action:
Ensure that the client is properly configured with the server's certificate.

WSM-00279
The following Fault Message is received at the client side from the service:- {0}. The client side policy is:- {4}. The service endpoint url is:- {3}. Keystore properties:- {1}. Properties found in the message context (Partial list):- {7}. PolicyReference OverrideProperty: {6} Policy configuration properties (some of these may be overridden by the properties passed in the PolicyReference or message context, for details about the order of precedence of properties consult documentation):- {5}. Other related information:- {2}.

Category:
Security

Cause:
Fault Message received at the client side from the service

Action:
Check the log file for possible causes.

WSM-00280
Caching of STS client executor failed which is required for secure conversation.

Category:
Security

Cause:
Caching of STS client executor failed which is required for se cure conversation.

Action:
Check error logs for more details.

WSM-00281
Failed to calculate session id for user {0}, due to {1}

Category:
Security

Cause:
Failed to calculate session id for user.

Action:
Check error logs for more details.

WSM-00282
Failed to calculate session id for user {0} because required credential "{1}" is NULL.

Category:
Security

Cause:
Failed to calculate session id because required credential is NULL.

Action:
Make sure that all required credentials are set.

WSM-00283
Failed to create token context required for secure conversation due to {0}

Category:
Security

Cause:
Failed to create token context which is required for secure conversation.

Action:
Check logs for finding out exact reason of failure.

WSM-00284
Failed to send secure conversation bootstrap request.

Category:
Security

Cause:
Failure occurred while trying to send secure conversation bootstrap request message, possibly due to a failure in security code.

Action:
Check logs for finding out exact reason of failure.

WSM-00285
Failed to issue secure conversation token due to : {0}.

Category:
Security

Cause:
Failed to issue secure conversation token.

Action:
Check logs for finding out exact reason of failure.

WSM-00286
Failed to renew secure conversation token.

Category:
Security

Cause:
Failed to renew secure conversation token.

Action:
Check logs for finding out exact reason of failure.

WSM-00287
Failed to cancel secure conversation token.

Category:
Security

Cause:
Failed to cancel secure conversation token.

Action:
Check logs for finding out exact reason of failure.

WSM-00288
SecurityContextToken required for secure conversation not found. You might have not enabled secure conversation on other side.

Category:
Security

Cause:
SecurityContextToken required for secure conversation not found.

Action:
Make sure that valid SCT is used for signing and encryption of message. You might have not enabled secure conversation on other side.

WSM-00289
SecurityContextToken version used for secure conversation is not matching with expected version. Expected : {0} but found namespace: {1}

Category:
Security

Cause:
SecurityContextToken version used for secure conversation is not matching with expected version.

Action:
Check documentation for supported WS Secure conversation version.

WSM-00290
SecurityContextToken version "{0}" used for secure conversation is not supported.

Category:
Security

Cause:
SecurityContextToken version used for secure conversation is not supported.

Action:
Check documentation for supported WS Secure conversation version.

WSM-00291
Failed to add addressing header to the secure conversation bootstrap message.

Category:
Security

Cause:
Failed to add addressing headers when creating secure conversation bootstrap message.

Action:
Check logs for finding out exact reason of failure.

WSM-00292
sc.lifetime property value given in secure conversation policy is not valid.

Category:
Security

Cause:
sc.lifetime property value "{0}" given in secure conversation policy is not valid.

Action:
sc.lifetime should have valid integer value.

WSM-00293
sc.lifetime property value given in domain configuration is not valid.

Category:
Security

Cause:
sc.lifetime property value "{0}" given in domain configuration is not valid.

Action:
sc.lifetime should have valid integer value.

WSM-00294
Secure Conversation token inclusion mechanism is not supported: {0}

Category:
Security

Cause:
Secure Conversation token inclusion mechanism is not supported.

Action:
Make sure to use supported token inclusion mechanism.

WSM-00295
Secure Conversation session has expired for SCT ID: {0}

Category:
Security

Cause:
Secure Conversation session has expired for SCT ID.

Action:
Renew session.

WSM-00296
Secure Conversation session not found in session manager for SCT ID: {0}

Category:
Security

Cause:
Secure Conversation session not found in session manager for SCT ID.

Action:
Check logs for the exact reason.

WSM-00297
Security Context Token in RSTR is null

Category:
Security

Cause:
Security Context Token in RSTR is null.

Action:
Check logs for the exact reason.

WSM-00298
Policy Reference URI(s) passed to dispatcher is empty.

Category:
Security

Cause:
Policy Reference URI(s) passed to dispatcher is empty.

Action:
Check logs for the exact reason.

WSM-00299
Exception is thrown by the Session Manager

Category:
Security

Cause:
Exception is thrown by the Session Manager.

Action:
Check logs for the exact reason.

WSM-00300
Invalid input to the Session Manager on {0}.

Category:
Security

Cause:
Invalid input to Session Manager.

Action:
Check logs for the exact reason.

WSM-00301
Error in creating session id since the reference resource pattern is null

Category:
Security

Cause:
Error in creating session id since the reference resource pattern is null

Action:
Check logs for the exact reason.

WSM-00302
Error in creating session id since the service URL in message context is null

Category:
Security

Cause:
Error in creating session id since the service URL in the message context is null

Action:
Check logs for the exact reason.

WSM-00303
Secure conversation is unsupported for the assertion {0}. The policy file should be checked to not have secure conversation "on" for this assertion.

Category:
Security

Cause:
Secure conversation is unsupported for this assertion.

Action:
Check your policy

WSM-00304
Message does not contain client entropy which is required by service policy.

Category:
Security

Cause:
Message does not contain client entropy while server policy requires it.

Action:
Check your client policy and make sure require-client-entropy is enabled on it.

WSM-00305
Session ID "{0}" removed from session manager because BadContextToken received. This happens because SecurityContextToken sent from client is not accepted by service which can be due to the time difference between client and service being more than configured clock skew and it can also happen if service is not using session persistence while client is.

Category:
Security

Cause:
BadContextToken fault received which is due to invalid or expired SecurityContextToken (SCT). This happens because SCT sent from client is not accepted by service which can be due to the time difference between client and service being more than configured clock skew and it can also happen if service is not using session persistence while client is.

Action:
Replay message again which will go through fine because dead session has been cleaned. Make sure that client and server clocks are synchronized properly or set correct clock skew. Also make sure that server and client are both configured with compatible session manager providers.

WSM-00306
The derived keys security token could not be obtained from the message.

Category:
Security

Cause:
The Derived keys could not be located

Action:
Either turn off the use-derived-keys flag or provide the derived keys in the message.

WSM-00307
Client Credential did not get delegated to the Service.

Category:
Security

Cause:
Client Credential did not get delegated to the Service.

Action:
Make sure the Kerberos configuration file on the client supports credential delegation.

WSM-00308
Conflicting client credential available from Config-Override and Credential Delegation.

Category:
Security

Cause:
Conflicting client credential available from Config-Override and Credential Delegation.

Action:
Either remove the client side config-overrides for Caller Principal Name and Keytab location or disable credential delegation.

WSM-00309
HTTP SPNEGO Authorization Header is missing in the request.

Category:
Security

Cause:
HTTP SPNEGO Authorization Header is missing in the request.

Action:
Client must provide a valid Authorization header for SPNEGO.

WSM-00310
Client Credential not available.

Category:
Security

Cause:
Client Credential not available.

Action:
Either provide caller principal name and keytab location or enable credential delegation if appropriate.

WSM-00311
SAML over HTTP authentication failure.

Category:
Security

Cause:
Failure occurred in SAML over HTTP authentication.

Action:
Use the appropriate GZIP and Base64 encoded combination of a valid SAML.

WSM-00312
Keystore reloading failed due to {0}

Category:
Security

Cause:
Reloading of the keystore failed.

Action:
Restart the server to load the latest keystore.

WSM-00313
Could not obtain the certificate for the corresponding thumbprint

Category:
Security

Cause:
The certificate for the corresponding SKI could not be obtained

Action:
Add the certificate to the Keystore.

WSM-00314
The Xpath transformation of the type "{0}" is not allowed. Only Xpath transformations of the type "{1}" are allowed. To allow all the Xpath transformations, set the property "{2}" to true.

Category:
Security

Cause:
The Xpath transformation present in the incoming SOAP message is not supported.

Action:
Make sure that incoming SOAP message contains only supported Xpath expressions, see the exception stack trace for details.

WSM-00315
The details of the keystore {0} removed from the system.

Category:
Security

Cause:
Removing the keystore details as keystore was replaced with a wrong one.

Action:
Replace the keystore with a valid one. After keystore has been replaced, it will be reloaded on next invocation.

WSM-00316
The CSF key "{0}" is reserved and can not be used for username credentials. Ensure that the reserved CSF key {1} is not used.

Category:
Security

Cause:
The CSF key being used is reserved and can not be used for username credentials.

Action:
Ensure that the reserved CSF keys are not used. Check error logs for more details.

WSM-00317
Required OES resource string is incomplete: application: {0}, resource_type: {1}, resource_name: {2}

Category:
Security

Cause:
Required OES resource string is incomplete.

Action:
Ensure that all components of resource string is available either dynamially or using config overrides.

WSM-00318
Required OES resource string is null because required resource pattern is null.

Category:
Security

Cause:
Required OES resource string is null because resource patterns is null.

Action:
Ensure that resource pattern is available which is passed from web service stack.

WSM-00319
Error while populating attributes for OES authorization. Actual error message is: {0}

Category:
Security

Cause:
Error occured while populating attributes for OES authorization.

Action:
Check logs for actual cause of error.

WSM-00320
PEPException has occurred while making authorization call to PDP using PEP API.

Category:
Security

Cause:
Error occured while invoking OES's authorization engine using PEP API.

Action:
Check logs for actual cause of PEP APIs failure.

WSM-00321
XPath attributes configured for fine-grained authorization will be ignored because no valid XML message found in current payload.

Category:
Security

Cause:
XPath attributes are being ignored because no SOAP message or XML msg found in current payload.

Action:
SOAP message should have valid envelope or if its SOA then XML request message should be available.

WSM-00322
Error occurred while evaluating XPath query. XPath query will be ignored. Specific error is: {0}

Category:
Security

Cause:
Error while evaluating XPath query. Query is being ignored.

Action:
Check logs if there is any error or XPath query may not be valid for current XML payload.

WSM-00323
STS {0} obtained from WSDL is {1}. Local STS configuration is also not available.

Category:
Security

Cause:
STS (issuer) uri is not available in the WSDL or client side STS configuration.

Action:
Ensure that STS trust config policy is attached to either the client or the service.

WSM-00324
Automatic (Client) Policy Configuration failed to determine a compatible client side policy to communicate with the STS at {0}.

Category:
Security

Cause:
Automatic (Client) Policy Configuration failed to determine compatible client side policy to communicate with STS.

Action:
Ensure that STS trust config service policy is attached and is configured with the correct issuer uri.

WSM-00325
The protocol "{0}" set in the token configuration for the token to be cached is not recognized. If the problem persists, contact Oracle Support Services.

Category:
Security

Cause:
The protocol set in the token configuration for the token to be cached is not recognized.

Action:
If the problem persists, contact Oracle Support Services.

WSM-00326
The client clock skew value should not be negative

Category:
Security

Cause:
Invalid client clock skew value.

Action:
Change client clock skew to a positive value.

WSM-00327
Incoming request did not have a valid authentication token. Service will send a 401 Challenge in response to the client with WWW-Authenticate header.

Category:
Security

Cause:
Incoming request did not have a valid authentication token.

Action:
Service will send a 401 Challenge in response to the client. Client should understand the authentication scheme and re-send the request with required token.

WSM-00328
The XPath expression {0} is not valid.

Category:
Security

Cause:
The XPATH expression could not be evaluated for the SOAP/XML Message. It could be because the xpath is not following xpath syntax.

Action:
THe XPATH expression is not valid, correct the XPATH and try again.

WSM-00329
The PII for the xpath {0} to be encrypted is already encrypted.

Category:
Security

Cause:
The PII Node to be encrypted is already encrypted. It could be because the same XPATH is being used twice or the message already had PII encrypted

Action:
Check if the same XPATH is being used again. There is some place where the PII policy should have been attached but was not attached properly.

WSM-00330
The XPATH {0} used to configure the PII does not result in TEXT_NODE.

Category:
Security

Cause:
The PII Xpath did not return a TEXT_NODE. If the Xpath does not return a TEXT_NODE then it is not a Supported XPATH

Action:
Rectify the XPATH configured for the PII so that it returns a TEXT_NODE.

WSM-00331
The key used to encrypt/decrypt PII could not derived.

Category:
Security

Cause:
The Secret Key for PII could not be derived. The policy is not configured properly

Action:
Rectify the PII configuration so that the secret key can be generated.

WSM-00332
The resource pattern is not configured properly.

Category:
Security

Cause:
The Resource Pattern is null.

Action:
The ResourcePattern should be properly configured.

WSM-00333
The PII policy is not supported on the SubjectType: {0}

Category:
Security

Cause:
PII Policy not supported on this SubjectType.

Action:
Dettach the PII policy from this subject as it is not supported here.

WSM-00334
The PII denoted by xpath {0} was encrypted in {1}, but was being decrypted in {2}, which is not allowed.

Category:
Security

Cause:
PII encrypted in one entity and decrypted in a different entity.

Action:
Attach the decrypt policy in the earlier entity, so that PII gets decrypted in the same entity where it was encrypted.

WSM-00335
Anonymous user found in the SAML assertion so anonymous subject has been created. Trusted issuers validation, DN list validation and other validations related to SAML token will be skipped. Subject: {0}

Category:
Security

Cause:
Anonymous user found in the SAML assertion so anonymous subject has been created. Trusted issuers validation, DN list validation and other validations related to SAML token will be skipped.

Action:
If anonymous user was not expected in token then check client's configuration.

WSM-00336
Anonymous user is being propagated as subject is {0}.

Category:
Security

Cause:
Anonymous user is being propagated as subject is either NULL or anonymous.

Action:
Check client's configuration if anonymous user should not be propagated.

WSM-00338
Error creating OPSS subject from username and policy context.

Category:
Security

Cause:
A failure occurred while creating OPSS subject from username and policy context.

Action:
Check log file for possible cause.

WSM-00339
Error creating anonymous subject.

Category:
Security

Cause:
A failure occurred while creating anonymous subject.

Action:
Check log file for possible cause.

WSM-00340
The key for the alias {0} not found in the KSS Keystore {1}. The following aliases are found in the Keystore: {2}

Category:
Configuration

Cause:
Key does not exist in the KSS keystore.

Action:
Ensure that alias exists in keystore and necessary permission to read key alias is granted.

WSM-00341
SAML assertion signature digest verification failed

Category:
Security

Cause:
SAML assertion signature verification failed.

Action:
Ensure that SAML assertion signature is valid.

WSM-00342
Certificate/Key with subject DN "{0}" has expired.

Category:
Security

Cause:
Certificate/Key has expired.

Action:
Get a new certificate/key.

WSM-00343
Could not get new Kerberos TGT and current TGT has expired.

Category:
Security

Cause:
Could not get new Kerberos TGT and current TGT has expired.

Action:
Check logs for the reason of failure. Principal and password (for example using keytab) must be available for login.

WSM-00344
Failed to authorize user request for {0}. {1}

Category:
Security

Cause:
Failed to authorize user request.

Action:
Check logs for the reason of failure and also check if required premission is granted.

WSM-00345
Failed to decrypt the encrypted key at client side due to {0}. Ensure that the client is configured with sign key as crypt key.

Category:
Security

Cause:
An error occurred while decrypting the encrypted key at client side.

Action:
Ensure that the client is configured with the sign key as crypt key.

WSM-00346
There is no matching assertion found in the service side policy which can process the incoming message. Ensure that there is a compatible policy attached at the client side. Tokens found in the security header are:- {0}. Authentication mechanism found in the HTTP header:- {1}. The assertions found in the service side policy are:- {2}.

Category:
Security

Cause:
No matching assertion found in the service side policy which can process the incoming message.

Action:
Ensure that a compatible client policy is attached and enabled at the client side.

WSM-00347
The request message contains the Derived Keys but service side policy is not configured to use Derived Keys for message decryption. Ensure that the service side policy is configured to use Derived Keys.

Category:
Security

Cause:
The request message contains the Derived Keys but service side policy is not configured to use Derived Keys for message decryption.

Action:
Ensure that the service side policy is configured to use Derived Keys.

WSM-00348
EncrytpedData element found inside the ReferenceParameters element. This might result in security vulnerabilities, so removing its data reference "{0}" from the reference list to avoid decryption of any EncrytpedData element inside the ReferenceParameters element. Ensure that the entire ReferenceParameters element is either encrypted or without any EncrytpedData element.

Category:
Security

Cause:
EncrytpedData element found inside the ReferenceParameters element. This might result in security vulnerabilities.

Action:
Ensure that the entire ReferenceParameters element is either encrypted or without any EncrytpedData element.

WSM-00349
The HTTP header is missing in the incoming client request message. Service will send back a 401 Challenge to the client with response header {0}: {1}.

Category:
Security

Cause:
Incoming request did not have any authentication token in the HTTP header.

Action:
Service will send back a 401 Challenge to the client. Client should understand one of the authentication schemes and re-send the request with one of the supported authentication token.

WSM-00350
The name attribute for the token issuer trust document is not found.

Category:
Security

Cause:
The name attribute for the token issuer trust document is not found.

Action:
Make sure the name is provided when creating a token issuer trust document.

WSM-00351
The tokentype attribute "{0}" for the Issuer in token issuer trust document is not supported.

Category:
Security

Cause:
The tokentype attribute for the Issuer in the token issuer trust document is not supported.

Action:
Change it to a supported token type when creating the Issuer in token issuer trust document.

WSM-00352
The keytype attribute "{0}" for a trusted key for an Issuer in the token issuer trust document is not supported.

Category:
Security

Cause:
The keytype attribute for a trusted key for an Issuer in the token issuer trust document is not supported.

Action:
Change it to a supported key type when creating the trusted key for the Issuer in token issuer trust document.

WSM-00353
The valuetype attribute "{0}" for a trusted key for an Issuer in the token issuer trust document is not supported.

Category:
Security

Cause:
The valuetype attribute for a trusted key for an Issuer in the token issuer trust document is not supported.

Action:
Change it to a supported key valuetype when creating the trusted key for the Issuer in token issuer trust document.

WSM-00354
The attribute "{0}" for which the filter is configured in a token attribute rule is not supported.

Category:
Security

Cause:
The attribute for which the filter is configured in a token attribute rule is not supported.

Action:
Set the filter only for supported attributes in a token attribute rule.

WSM-00355
Name Id "{0}" in the token is not allowed by the token attribute rule for the DN "{1}".

Category:
Security

Cause:
Token Name ID validation for the DN failed.

Action:
Name ID value is not allowed for the DN of token signing certificate. Make sure a valid user is sent.

WSM-00356
Failed to enforce token attribute rule "{0}" configured for the DN "{1}" of the signing certificate.

Category:
Security

Cause:
Token attribute rule configured for the DN of the signing certificate failed.

Action:
Check logs for the details. Either rule is not configured properly or token does not has required details to enforce it.

WSM-00357
Token attribute rule identifier "{0}" is not associated with any trusted key of a trusted token issuer.

Category:
Security

Cause:
Token attribute rule identifier "{0}" is not assocoated with any trusted key of a trusted token issuer.

Action:
Check the identifier to make sure it matches the key identifier value of a trusted key for an trusted issuer configured.

WSM-00358
SAML assertion signature reference is pointing to invalid URI

Category:
Security

Cause:
SAML assertion signature reference is pointing to invalid URI .

Action:
Ensure that SAML assertion signature is valid

WSM-00359
Instance tenancy is not available but used as property value: "{0}"

Category:
Security

Cause:
Instance tenancy is not available.

Action:
Make sure that instance tenancy is available or don't use that property if not required.

WSM-00360
Tenant name set in configuration property "{0}" does not match with tenancy: "{1}" of current subject.

Category:
Security

Cause:
Tenant name set in configuration property does not match with current subject's tenancy.

Action:
Make sure that tenant name set as configuration property matches with current subject's tenant name.

WSM-00361
The SAML HOK token found in the incoming message does not contain the KeyInfo element. Make sure that the incoming message contains a valid SAML HOK assertion and contains the KeyInfo element.

Category:
Security

Cause:
The SAML HOK assertion found in the incoming message does not contain the KeyInfo element.

Action:
Insert valid SAML HOK assertion containing the KeyInfo element and resend the request.

WSM-00362
The SAML HOK token found in the incoming message does not contain the KeyValue element. Make sure that the incoming message contains a valid SAML HOK assertion and contains the KeyValue element.

Category:
Security

Cause:
The SAML HOK token found in the incoming message does not contain the KeyValue element.

Action:
Insert valid SAML HOK token containing the KeyValue element and resend the request.

WSM-00363
The SAML token found in the incoming message is not valid. Both AttributeStatement and AuthenticationStatement elements are missing from the SAML assertion.

Category:
Security

Cause:
The SAML token found in the incoming message is not valid. Both AttributeStatement and AuthenticationStatement elements are missing from the SAML assertion.

Action:
Insert valid SAML token and resend the request.

WSM-00364
JWT token has expired

Category:
Security

Cause:
JWT token received after the token has expired.

Action:
Fix the expiry claim and retry the operation.

WSM-00365
JWT token issuer - "{0}" is not trusted. Configured trusted issuers are "{1}"

Category:
Security

Cause:
JWT token issuer is not trusted.

Action:
Fix the issuer claim and retry the operation.

WSM-00366
JWT symmetric key "{0}" is not trusted

Category:
Security

Cause:
JWT key id is not trusted.

Action:
Fix the symmetric key and retry the operation.

WSM-00367
JWT certificate DN "{0}" is not trusted

Category:
Security

Cause:
JWT certificate DN is not trusted.

Action:
Fix the JWT certificate and retry the operation.

WSM-00368
JWT x5t claim is invalid

Category:
Security

Cause:
Cannot find certificate matching the JWT x5t claim.

Action:
Fix the JWT x5t claim and retry the operation.

WSM-00369
JWT signature csf key is not configured

Category:
Configuration

Cause:
Cannot find JWT signature csf key.

Action:
Fix the JWT signature csf key and retry the operation.

WSM-00370
JWT token is not signed

Category:
Security

Cause:
JWT token is not signed.

Action:
Sign the JWT token and retry the operation.

WSM-00371
JWT signature algorithm mismatch, expecting "{0}", found "{1}"

Category:
Security

Cause:
JWT signature algorithm does not match policy.

Action:
Fix the JWT signature algorithm and retry the operation.

WSM-00372
Unsupported signature algorithm specified

Category:
Security

Cause:
An unsupported signature algorithm was provided.

Action:
Consult the documentation for the supported signature algorithms and retry the operation.

WSM-00373
JWT audience claim - "{0}" is invalid. Audience conditions are not satisfied. "{1}"

Category:
Security

Cause:
JWT audience claim is invalid

Action:
Fix the audience claim to match the resource and retry the operation.

WSM-00374
JWT issued time claim is invalid

Category:
Security

Cause:
JWT token received before the issued time.

Action:
Fix the issued time claim and retry the operation.

WSM-00375
Unable to determine user tenant name in multi-tenant environment

Category:
Security

Cause:
Unable to determine user tenant name in multi-tenant environment.

Action:
Ensure that the user tenant name is set.

WSM-00376
SAML token authentication failed for issuer "{0}"

Category:
Security

Cause:
SAML token based authentication failed.

Action:
SAML token based authentication failed. Check logs for more details.

WSM-00377
{0}. This error is most likely due to secure conversation not enabled at the service side policy

Category:
Security

Cause:
Secure conversation is not enabled at the service side policy.

Action:
Disable secure conversation at the client side policy and try again.

WSM-00378
Incoming Kerberos token has an invalid/unsupported Value Type: {0} : {1}

Category:
Security

Cause:
The value type of the incoming Kerberos token did not match the expected type at service side.

Action:
Make sure client sends the Kerberos token of value type as expected by service policy.

WSM-00379
There are no Xpath transformations allowed inside CipherReference in EncryptedKey. To allow all the Xpath transformations, set the property {0} to true.

Category:
Security

Cause:
No Xpath transformations are supported inside CipherReference in EncryptedKey which are present in the incoming SOAP message.

Action:
Do not include any XPATH transformations inside CipherReference

WSM-00380
An Exception was thrown while retreiving the keystore password from the credential store.

Category:
Security

Cause:
The Keystore password was not retrieved

Action:
Check if the keystore password is configured correctly.

WSM-00381
Alias "{0}" is not valid for the keystore entry.

Category:
Security

Cause:
Alias doesn't point to any trusted certificate or a private key entry.

Action:
Ensure that alias either points to any trusted certificate or a private key entry and retry the operation.

WSM-00382
An Exception was thrown while loading the keystore, only JKS type keystores are supported by the oracle.wsm.security.store.jks.mgmt.KeystoreMBean.

Category:
Configuration

Cause:
Keystore MBean only support JKS type keystore.

Action:
Consult the oracle documentation to ensure that keystore.type that is configured is of type JKS for the oracle.wsm.security.store.jks.mgmt.KeystoreMBean.

WSM-00383
Failed to initialize JKS Mbean auditor.

Category:
Security

Cause:
An internal error occurred; failed to initialize the auditor.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-00384
Alias "{0}" points to a certificate which is not a trusted certificate.

Category:
Security

Cause:
Alias already exists but does not identify an entry containing a trusted certificate.

Action:
Check that a trusted certificate already exists for the given alias and retry the operation.

WSM-00385
Alias "{0}" does not point to a valid private key entry in the keystore.

Category:
Security

Cause:
Alias doesn't point to a private key entry.

Action:
Ensure that alias points to a private key entry in the keystore.

WSM-00386
Invalid type argument "{0}". Valid values are "Certificate" and "PKCS7".

Category:
Security

Cause:
Invalid type argument. Valid values are "Certificate" for single certificate and "PKCS7" for certificate chain.

Action:
Ensure that either "Certificate" or "PKCS7" is passed as type argument.

WSM-00387
No trusted certificate identified by alias "{0}".

Category:
Security

Cause:
No trusted certificate entry identified by the alias.

Action:
Ensure that alias points to a trusted certificate and retry the operation.

WSM-00388
Certificate deletion failed for "{0}" alias(es).

Category:
Security

Cause:
An error occurred while deleting the alias.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-00389
Public key entry of the certificate to be imported does not match the existing public key entry in the keystore for alias "{0}".

Category:
Security

Cause:
The public key in the certificate does not match the one in the keystore.

Action:
Ensure that the certificate is imported into the alias used for generating certificate request.

WSM-00390
Failed to retrieve Private key entry for alias "{0}" due to invalid password.

Category:
Security

Cause:
Failed to retrieve private key entry due to invalid password.

Action:
Ensure that correct password is used to import/set the certificate.

WSM-00391
Creating certificate from base64 encoded string failed for alias "{0}".

Category:
Configuration

Cause:
Encountered error while creating certificate from base64 encoded string.

Action:
Must provide valid certificate in valid base64 encoded string.

WSM-00392
Failed to store keystore to the file system.

Category:
Configuration

Cause:
Encountered error while storing the keystore to the file system.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-00393
Permission "{0}" required to access the application specific CSF map "{1}" is not granted to the resource "{2}". Underlying exception message : "{3}"

Category:
Security

Cause:
Permission required to access application specific credential map is not granted.

Action:
Grant permission for accessing application specific credential map to the codesource and retry the operation.

WSM-00394
The given name "{0}" for permission "{1}" with action "{2}" is not supported target format. If action is "assert", supported target format is resource={RESOURCENAME}. If action is "getKey", supported target format is resource={RESOURCENAME},mapName={CSF_MAP_NAME}.

Category:
Security

Cause:
The target format of the specified WSIdentityPermission is not supported.

Action:
Correct the supported target terms for WSIdentityPermission and retry the operation.

WSM-00395
The action "{0}" is not supported for permission "{1}".

Category:
Security

Cause:
The action of the specified WSIdentityPermission is not supported.

Action:
Correct the supported actions for WSIdentityPermission and retry the operation.

WSM-00396
JKS "{0}" audit operation failed.

Category:
Configuration

Cause:
Encountered error while auditing JKS operation.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-00397
JKS Mbean registration failed.

Category:
Security

Cause:
JKS Mbean registration failed.

Action:
Check logs for actual cause of Mbean registration failure.

WSM-00398
The OAuth2 policy configuration property token-uri has an invalid value of "{0}". The value must point to a valid Oauth token endpoint and should be specified in the form "http(s)://host:port/tokens"; it should not be a null or empty string.

Category:
Configuration

Cause:
OAuth2 config attribute token-uri is either null, empty or not in the format of "http(s)://host:port/tokens".

Action:
Provide valid attribute value for Oauth token endpoint which is in the format of "http(s)://host:port/tokens".

WSM-00399
OAuth2 request sent to OAuth2 server failed with Message : "{0}". Please check OAuth2 server logs for more details.

Category:
Security

Cause:
OAuth2 token request failed

Action:
Check the OAuth2 Server logs and exception stack trace to determine why the request failed.

WSM-00400
OAuth2 server responded with status : "{0} {1}", error : "{2}". Please check OAuth2 server logs for more details. Additional info: Token URI - "{3}", Client ID - "{4}", Scope - "{5}".

Category:
Security

Cause:
OAuth2 server responded with error message and bad request

Action:
Check the error message returned by OAuth2 server to determine why the request was rejected.

WSM-00401
JWT signature verification failed.

Category:
Security

Cause:
JWT Signature verification failed

Action:
Fix the JWT token or import the right trusted issuer certificate and retry the operation.

WSM-00402
JWT kid "{0}" claim is not valid. Certificate mathcing the kid claim does not exist in OWSM trust store.

Category:
Security

Cause:
Cannot find certificate matching the JWT kid claim.

Action:
Fix the JWT kid claim or import the certificate in OWSM trust store and retry the operation.

WSM-00403
oauth2_config_client_policy is not found. Attach it using GPA or LPA.

Category:
Configuration

Cause:
The oauth2_config_client_policy is not attached.

Action:
Check the configuration and attach oauth2_config_client_policy using GPA or LPA.

WSM-00404
Provide valid value for oauth2.client.csf.key config override.

Category:
Configuration

Cause:
oauth2.client.csf.key config override is missing.

Action:
Provide valid value for oauth2.client.csf.key after adding entry in CSF.

WSM-00405
Add a CSF entry with client id

Category:
Configuration

Cause:
oauth2.client.csf.key config override does not point to a valid entry

Action:
Add an entry in CSF corresponding to oauth2.client.csf.key.

WSM-00406
Configured redirect.uri = "{0}" is invalid .Configure a valid redirect.uri value for 3-legged OAuth

Category:
Configuration

Cause:
redirect.uri config override does not point to a valid value

Action:
Configure redirect.uri in the config override

WSM-00407
Invalid policy alternatives found inside XOR policy operator. It contains two or more message protection assertions ({0}, {1}) which have same authentication token type.

Category:
Configuration

Cause:
Invalid policy alternatives found inside XOR policy operator. It contains two or more message protection assertions which have same authentication token type.

Action:
Ensure that you have only one message protection assertion with same authentication token type in the XOR policy

WSM-00408
Invalid policy alternatives found inside XOR policy operator. It contains two or more non message protection or SSL assertions ({0}, {1}) which have same authentication token type.

Category:
Configuration

Cause:
Invalid policy alternatives found inside XOR policy operator. It contains two or more non message protection or SSL assertions which have same authentication token type.

Action:
Ensure that you have only one non message protection assertion with same authentication token type in the XOR policy

WSM-00409
Invalid policy alternatives found inside XOR policy operator. It contains more than one of x509, anonymous or custom authentication token type ({0}, {1}).

Category:
Configuration

Cause:
Invalid policy alternatives found inside XOR policy operator. It contains more than one of x509, anonymous or custom authentication token type.

Action:
Ensure that you have only one of either x509, anonymous or custom authentication token types in the XOR policy

WSM-00410
Invalid policy alternatives found inside XOR policy operator. It contains two or more secure conversation enabled message protection assertions ({0}, {1}) which have same authentication token type.

Category:
Configuration

Cause:
Invalid policy alternatives found inside XOR policy operator. It contains two or more secure conversation enabled message protection assertions which have same authentication token type.

Action:
Ensure that you have only one secure conversation enabled message protection assertion with same authentication token type in the XOR policy

WSM-00411
Invalid policy alternatives found inside XOR policy operator. It contains two or more secure conversation enabled SSL assertions ({0}, {1}) which have same authentication token type.

Category:
Configuration

Cause:
Invalid policy alternatives found inside XOR policy operator. It contains two or more secure conversation enabled SSL assertions which have same authentication token type.

Action:
Ensure that you have only one secure conversation enabled SSL assertion with same authentication token type in the XOR policy

WSM-00412
Invalid policy alternatives found inside XOR policy operator. It contains more than one secure conversation enabled assertion with either x509, anonymous or custom authentication token types ({0}, {1}).

Category:
Configuration

Cause:
Invalid policy alternatives found inside XOR policy operator. It contains more than one secure conversation enabled assertion with x509, anonymous or custom authentication token type.

Action:
Ensure that you have only one secure conversation enabled assertion with either x509, anonymous or custom authentication token types in the XOR policy

WSM-00413
Invalid policy alternatives found inside XOR policy operator. It contains two or more message protection assertions which have different values for keystore.enc.csf.key ({0}, {1}).

Category:
Configuration

Cause:
Invalid policy alternatives found inside XOR policy operator. It contains two or more message protection assertions which have different values for keystore.enc.csf.key property.

Action:
Ensure that you have same value for keystore.enc.csf.key for all message protetcion assertions

WSM-00414
DMS string not available in ClientConfig properties. Setting dummy value for OWSM agent initialization. Monitoring will not work for subject identified by {0}

Category:
Security

Cause:
DMS string not available in ClientConfig properties.

Action:
Set the WSMExecutionConstants.AGENT_TOPOLOGYNODE_PATH proeprty with a String value in the ClientConfig object of the Jersey Client.

WSM-00415
The value of algorithm suite,"{0}" used in the JWT assertion is not valid. The only valid value to be used is "{1}".

Category:
Security

Cause:
The algorithm suite specified in the policy is not supported by JWT policies. Only Asymmetric key signature is supported at this time.

Action:
Make sure that a valid value of algorithm-suite is provided in the JWT assertion.

WSM-00416
The current server time is "{0}", incoming message creation time is "{1}", incoming message expiry time is "{2}" , configured clock skew is "{3}" seconds. The acceptable time range is "{4}"

to "{5}". The incoming token is outside the valid range as allowed by clock skew and expiry times.

Category:
Security

Cause:
The incoming message is outside the valid range as allowed by clock skew and expiry times.

Action:
Make sure the token is not expired. Check the allowed clock skew and configure them as required.

WSM-00417
Alias "{0}" already exists in the Keystore.

Category:
Security

Cause:
Alias already points to trusted certificate or a private key entry.

Action:
Ensure that alias do not already exist in the Keystore and retry the operation.

WSM-00418
Subject Name Identifier is missing in the SAML token. Check if the user identifier is properly set up to be included in the SAML assertion.

Category:
Security

Cause:
Subject Name Identifier is missing in the SAML token.

Action:
Check if the user identifier is properly set up to be included in the SAML assertion.

WSM-00419
Keystore properties updation failed due to {0}

Category:
Security

Cause:
Check nested error for failure

Action:
Check nested error for fixing the issue

WSM-00420
The key, {0}, is not retrieved due to exception "{4}". The location of the key store being used is "{1}" and its type is "{2}". The following aliases are found in the keystore:- {3}

Category:
Configuration

Cause:
Error occurred while obtaining key from store.

Action:
Make sure the key exists in the keystore. Check JPS configuration settings for correct key alias, key password and keystore password. Also, check the values of the key keystore-csf-key and its password in the oracle.wsm.security map, through EM or WLST. In a rare situation, this error can also happen if the actual keystore type is ORACLE_WALLET and the keystore type specified in JPS configuration file is PKCS12.

WSM-00421
The claim "{0}" contains null or empty value in the JWT token "{1}".

Category:
Security

Cause:
The claim contains empty or null value in the incoming JWT token.

Action:
Make sure that the claim is present in the incoming JWT token.

WSM-00422
Message is not compliant with timestamp requirement of the policy. Policy indicates that the timestamp element should not be present, but it is found in the message.

Category:
Security

Cause:
Timestamp policy compliance failed. Policy indicates that the timestamp element should not be present, but it is found in the message.

Action:
Check the message and make sure message is compliant with timestamp requirement of the service policy.

WSM-00423
Web service authentication failed.

Category:
Security

Cause:
Web Service Authentication failed at the server end.

Action:
Resend valid credentials.

WSM-00424
The init-param named servlet-name not found in the deployment descriptor. Skipping SecurityFilter initialization. OWSM SecurityFilter will not be enforced.

Category:
Security

Cause:
servlet-name init param for the OWSM security filter definition was missing from the application's web.xml.

Action:
User must provide a value for the servlet-name init param of the filter definition in the web.xml for the OWSM Security Filter to be initialized.

WSM-00425
The security header is missing in request. Ensure that there is a valid security policy attached at the client side, and the policy is enabled. And make sure timestamp is present in the security header.

Category:
Security

Cause:
Security header was expected but was not found.

Action:
Security header is missing in request. It could be that client side policy has not been applied. Resend request with appropriate Security header. And make sure timestamp is present in the security header.

WSM-00426
The security header is missing in response. Ensure that response message is compliant with security requirement of the client policy. And make sure timestamp is present in the security header.

Category:
Security

Cause:
Security header was expected but was not found.

Action:
Security header is missing in response. The response message is not compliant with security requirement of the client policy. Check the response message sent by service. And make sure timestamp is present in the security header.

WSM-00427
Security Exception : {0}

Category:
Security

Cause:
The system encountered a failure while enforcing security.

Action:
Check diagnostic log file to get more details.

WSM-00428
The certificate for the alias {0} not found in the KSS Keystore {1}. The following aliases are found in the Keystore: {2}

Category:
Configuration

Cause:
Certificate does not exist in the KSS keystore.

Action:
Ensure that certificate exists in keystore

WSM-00429
The value of the name id attribute {0} present in the token is not of type string.

Category:
Configuration

Cause:
name id attribute value present in the token is not of string type.

Action:
Ensure that name id attribute value is of type string in the token.

WSM-00430
Signature not present in the SAML Assertion.

Category:
Security

Cause:
Signature not present in the SAML Assertion.

Action:
Check to see that the SAML Assertion is signed or turn off saml.enveloped.signature.required.

WSM-00431
Provide valid value for oauth1.client.csf.key config override.

Category:
Configuration

Cause:
oauth1.client.csf.key config override is missing.

Action:
Provide valid value for oauth1.client.csf.key after adding entry in CSF.

WSM-00432
The property "{0}" is not found in the incoming message context.

Category:
Configuration

Cause:
The message contains empty or null value for the property in the incoming message context.

Action:
Make sure that the property is present in the incoming message context.

WSM-00433
HTTP Request type "{0}" is invalid. Valid values are GET and POST.

Category:
Configuration

Cause:
The HTTP Request type was invalid.

Action:
Valid supported values are GET and POST

WSM-00434
Entity type "{0}" is invalid. Only type Form corresponding to Content-Type application/x-www-form-urlencoded is supported.

Category:
Configuration

Cause:
Entity type is invalid. Only type Form corresponding to Content-Type application/x-www-form-urlencoded is supported.

Action:
Use Content-Type application/x-www-form-urlencoded and corresponding class object

WSM-00435
Message type "{0}" is invalid. Only REST is supported for oauth1 client policy.

Category:
Configuration

Cause:
Message type is invalid. Only REST is supported.

Action:
Use REST for using oauth1 policy

WSM-00436
Provide valid value for csf-key config override.

Category:
Configuration

Cause:
csf-key config override is missing.

Action:
Provide valid value for csf-key after adding entry in CSF.

WSM-00437
Virtual user is being propagated as subject is {0}.

Category:
Security

Cause:
Subject based on virtual user is being propagated.

Action:
Check client's configuration if virtual user should not be propagated.

WSM-00438
Failure occurred while performing signature caching validation.

Category:
Security

Cause:
Failure occurred while performing signature caching validation.

Action:
This may be due to same message being replayed. SignatureValue entry is found in the Signature Replay Cache. Resend the request with a valid signature.

WSM-00439
Algorithm Suite mismatch, expecting "{1}", found "{0}".

Category:
Security

Cause:
UsernameToken with Password Derived Keys Assertion had algorithm-suite other than Basic128.

Action:
UsernameToken with Password Derived Keys supports only BASIC128 algorithm suite.Set algorithm-suite as Basic128.

WSM-00440
Both Signed and Encrypted parts not allowed when using password derived keys support .

Category:
Security

Cause:
Both Signing and Encryption not supported for UsernameToken with Password Derived Keys Policy.

Action:
Make sure policy does not have both signed and encrypted parts.

WSM-00441
The iterations value provided by the user: "{0}" is not valid. The default value of 1000 is being used .

Category:
Security

Cause:
The Iteration value provided by the user is not valid

Action:
Provide a valid value. Till then the default value 1000 will be used.

WSM-00442
The {0} token found in the request, Encoded token: [{1}] Decoded token: [{2}] is invalid and token authentication failed

Category:
Security

Cause:
Improper security token/assertion in the request found during authentication.

Action:
Check the security token/assertion in the request.

WSM-00443
The HTTP USER header from OAM is missing.

Category:
Security

Cause:
The User Header was not found.

Action:
Ensure that the request HTTP headers contain an User header from OAM.

WSM-00444
Public keys using open id connect discovery document could not be trusted for issuer {0}.

Category:
Security

Cause:
Cannot configure jwk trust with the issuer.

Action:
Check the logs and retry the operation.

WSM-00445
The key type of the public key is not supported. Only RSA is supported.

Category:
Security

Cause:
JWK key type of the key is not trusted. Only RSA is supported.

Action:
Check the kty param of JWK document and retry the operation.

WSM-00447
Kid {0} is not a valid a trusted kid for issuer {1}.

Category:
Security

Cause:
JWK key id is not trusted.

Action:
Import the JWK through CLI or REST API.

WSM-00448
Public key required for signature verification could not be retrieved for kid {0} from both local JWK as well as remotely configured JWK.

Category:
Security

Cause:
kid is not present in the JWT token.

Action:
Check kid present in the JWT.

WSM-00449
kid attribute is missing in the JWT token.

Category:
Security

Cause:
The kid attribute is missing in the JWT Token.

Action:
Check the JWK token and try again.

WSM-00450
The JWK url is not configured.

Category:
Security

Cause:
The JWK URL is not configured.

Action:
Configure the JWK trust using REST or CLI command.

WSM-00451
JWK or Certificate based trust is not configured.

Category:
Security

Cause:
JWK or Certificate based trust is not configured

Action:
Configure the JWK or Certificate based trust using REST or CLI command.

WSM-00452
Failure in looking up requested Runtime MBean Server of the Weblogic Server where this application is running because the JNDI name used, "{0}", is wrong.

Category:
Security

Cause:
Failure occurred in looking up or connecting to the requested Runtime MBean server on the Weblogic server.

Action:
Make sure that the right JNDI name for the Runtime MBean server is passed for the lookup and retry the operation.

WSM-00453
Failure in identifying the correct object name of the Runtime Service MBean for this Weblogic server because the String provided, "{0}", does not correspond to a valid object-name representing the WLS Runtime Service MBean.

Category:
Security

Cause:
Failure occurred in identifying the correct object name of the Runtime Service MBean for this Weblogic server.

Action:
Make sure that the String representing the object-name of the Runtime Service MBean is correct.

WSM-00454
JWT audience claim - "{0}" is invalid. The value of resource tenancy "{1}" is not same as tenant claim "{2}"

Category:
Security

Cause:
JWT audience claim is invalid

Action:
Fix the audience claim to match the resource tenancy with tenant claim and retry the operation.

WSM-00455
JWT audience claim - "{0}" is invalid. Necessary Audience condition is not satisfied. "{1}"

Category:
Security

Cause:
JWT necessary audience claim is not satisfied

Action:
Fix the audience claim to match the resource and retry the operation.

WSM-00456
Failure occurred while looking for a specific MBean or attribute in the Runtime Service MBean, "{0}", for this Weblogic server. See the exception for more details.

Category:
Security

Cause:
Failure occurred while looking for a specific MBean or attribute in the Runtime Service MBean for this Weblogic server.

Action:
Make sure that the MBean name or attribute name being looked for is correct.

WSM-00457
Credential could not be found for csf key "{0}" under csf map "{1}".

Category:
Other

Cause:
Credentials are not found in the credential store..

Action:
Check for credentials in the credential store..

WSM-00458
Could not connect to "{0}". Server returned HTTP Code: {1}.

Category:
Other

Cause:
Incorrect response code is recieved.

Action:
Check if URL endpoint is correct and is serving content.

WSM-00459
Failure occurred while trying to authenticate an incoming Basic Auth header on behalf of Weblogic server. See the exception for more details.

Category:
Security

Cause:
Failure occurred while trying to authenticate incoming Basic Auth header on behalf of Weblogic server.

Action:
Make sure that valid credentials are being used to generate the request.

WSM-00460
JWT token verification failed.

Category:
Security

Cause:
JWT Token verification failed

Action:
Fix the JWT token and retry the operation.

WSM-00461
Global configuration for IDCS issuer is invalid with incorrect baseURL={0} or idcsClientCsfKey={1}. It might not have been configured

Category:
Security

Cause:
Global configuration for IDCS issuer is invalid. It might not have been correctly configured

Action:
check the global configuration and retry the operation.

WSM-00462
Global configuration for IDCS issuer is not present. Hence unable to retrieve baseURL and idcsClientCsfKey

Category:
Security

Cause:
Global configuration for IDCS issuer is not present.

Action:
create the global configuration and retry the operation.

WSM-00463
Service instance app name is not present in HTTP header. This is required for retrieving TAGS configuration from IDCS.

Category:
Security

Cause:
Service instance app name is not present in HTTP header. This is required for retrieving TAGS configuration from IDCS.

Action:
configure the client to send service instance app name and retry the operation.

WSM-00464
Resource tenancy is not present in HTTP header. This is required for retrieving TAGS configuration from IDCS.

Category:
Security

Cause:
Resource Tenancy is not present in HTTP header. This is required for retrieving TAGS configuration from IDCS.

Action:
configure the client to send resource tenancy and retry the operation.

WSM-00465
Failure occurred while trying to retieve tags from IDCS due to {0}

Category:
Security

Cause:
Failure occurred while trying to retrieve tags from IDCS.

Action:
Make sure that IDCS is up and has tags configured.

WSM-00466
Error parsing refresh interval {0}, using default value...

Category:
Security

Cause:
Error parsing refresh interval.

Action:
Make sure that refreshInterval is a valid integer value.

WSM-00467
Failed retrieving IDCS Discovery Metadata for {0} info from {1}.

Category:
Security

Cause:
Failed retrieving IDCS Discovery Metadata.

Action:
Make sure that IDCS is up and running.

WSM-00468
Error locating service with HK2: {0}

Category:
Security

Cause:
Failure in locating service.

Action:
Make sure that services are properly configured with HK2.

WSM-00469
Failure occurred while trying to get access token from IDCS due to {0}

Category:
Security

Cause:
Failure occurred while trying to retrieve access token from IDCS.

Action:
Make sure that IDCS is up and credentials are correct.

WSM-00470
Error processing tags with TAG data used: {0}

Category:
Security

Cause:
Failed processing tags.

Action:
Analyze the data.

WSM-00471
JWT audience claim - "{0}" is invalid. Custom necessary audience condition returns NULL result on evaluation

Category:
Security

Cause:
JWT necessary audience claim is not satisfied as the implementation of custom condition not correct

Action:
Fix the custom audience condition implementation and retry the operation.

WSM-00472
Required policy configuration scope is missing for OAuth2 three-legged policy. Configure a valid scope value

Category:
Security

Cause:
Required policy configuration scope is missing for OAuth2 three-legged policy.

Action:
Configure policy with a valid scope config override.

WSM-00473
State is not present in the response received from OAuth2 server for the request for authorization code for 3-legged flow. Hence rejecting the response.

Category:
Security

Cause:
State is not present in the response received from OAuth2 server for the request for authorization code for 3-legged flow.

Action:
Resend the request.

WSM-00474
State is not valid in the response received from OAuth2 server for the request for authorization code for 3-legged flow. Hence rejecting the response.

Category:
Security

Cause:
State is not valid in the response received from OAuth2 server for the request for authorization code for 3-legged flow.

Action:
Resend the request.

WSM-00475
Error initializing servlet filter for 3-legged flow.

Category:
Security

Cause:
There was error in initializing servlet filter for 3-legged flow.

Action:
Check the server for application deployment logs.

WSM-00476
Error in redirecting incoming request to original address for 3-legged flow.

Category:
Security

Cause:
There was error in redirecting incoming request to original address for 3-legged flow.

Action:
Check the server for application deployment logs.

WSM-00477
Servlet Filter Exception while enforcing 3-legged OAuth security

Category:
Security

Cause:
The system encountered a failure while enforcing security in the servlet filter for 3-legged flow.

Action:
Check diagnostic log file to get more details.

WSM-00478
Error in enforcing security for OAuth2 3-legged flow. Please check the logs for more details.

Category:
Security

Cause:
The system encountered a failure while enforcing security in the servlet filter for 3-legged flow.

Action:
Check diagnostic log file to get more details.

WSM-00479
There is no incoming authorization code found but the policy is configured for 3-legged flow.

Category:
Security

Cause:
There is no incoming authorization code found but the policy is configured for 3-legged flow.

Action:
Configure the required filters to obtain authorization code.

WSM-00481
Configured authorization.uri = "{0}" is invalid .Configure a valid authorization.uri value for 3-legged OAuth

Category:
Configuration

Cause:
authorization.uri config override does not point to a valid value

Action:
Configure authorization.uri in the config override

WSM-01501
failure in parsing the policy attachment

Category:
Data

Cause:
The XML was not well formed, or the XML did not follow the policy attachment schema.

Action:
Ensure that the XML is well formed, and the XML follows the policy attachment schema.

WSM-01502
failure in parsing the assertion template

Category:
Data

Cause:
The XML was not well formed, or the XML did not follow the assertion template schema.

Action:
Ensure that the XML is well formed, and the XML follows the assertion template schema.

WSM-01503
failure in parsing the assertion

Category:
Data

Cause:
The XML was not well formed, or the XML did not follow the assertion schema.

Action:
Ensure that the XML is well formed, and the XML follows the assertion schema.

WSM-01504
failure in parsing the property set configuration

Category:
Data

Cause:
The XML was not well formed, or the XML did not follow the property set Config schema.

Action:
Ensure that the XML is well formed, and the XML follows the property set Config schema.

WSM-01505
failure in creating a copy of the policy {0}

Category:
Data

Cause:
Copying of the policy failed.

Action:
Ensure that the policy to be copied is valid. If the problem persists, contact Oracle Support Services.

WSM-01506
failure in creating a copy of the assertion template {0}

Category:
Data

Cause:
Copying of the assertion template failed.

Action:
Ensure that the assertion template to be copied is valid. If the problem persists, contact Oracle Support Services.

WSM-01507
failure in creating a copy of the assertion {0}

Category:
Data

Cause:
Copying of the assertion failed.

Action:
Ensure that the assertion to be copied is valid. If the problem persists, contact Oracle Support Services.

WSM-01508
failure in transforming policy {0} to XML

Category:
Data

Cause:
The policy could not be serialized to XML.

Action:
Ensure that the policy Java object can be serialized to XML format.

WSM-01509
failure in transforming policy set {0} to XML

Category:
Data

Cause:
The policy set could not be serialized to XML.

Action:
Ensure that the policy set Java object can be serialized to XML format.

WSM-01510
failure in transforming policy attachment {0} to XML

Category:
Data

Cause:
The policy attachment could not be serialized to XML.

Action:
Ensure that the policy attachment Java object can be serialized to XML format.

WSM-01511
failure in transforming assertion template {0} to XML

Category:
Data

Cause:
The assertion template could not be serialized to XML.

Action:
Ensure that the assertion template Java object can be serialized to XML format.

WSM-01512
failure in transforming assertion {0} to XML

Category:
Data

Cause:
The assertion could not be serialized to XML.

Action:
Ensure that the assertion Java object can be serialized to XML format.

WSM-01513
failure in transforming configuration {0} to XML

Category:
Data

Cause:
The configuration could not be serialized to XML.

Action:
Ensure that the configuration Java object can be serialized to XML format.

WSM-01514
failure in transforming policy reference {0} to XML

Category:
Data

Cause:
System could not serialize policy reference to XML.

Action:
Ensure passed policy reference Java object doesn't have issues that causes the serialization to XML to fail.

WSM-01515
failure in transforming policy subject {0} to XML

Category:
Data

Cause:
System could not serialize policy subject to XML.

Action:
Ensure passed policy subject Java object doesn't have issues that cause the serialization to XML to fail.

WSM-01524
failure in serialization of WSDL

Category:
Data

Cause:
WSDL Serialization failed.

Action:
Ensure WSDL Extensions are available and configured. Consult diagnostic log for details or contact Oracle Support Services.

WSM-01526
WSDL Definition object is null

Category:
Data

Cause:
WSDL Definition Object is not available

Action:
Ensure that a valid WSDL Definition object is sent to OWSM for advertisement of wsdl.

WSM-01527
Failed to advertise policy for tenant context {0} due to underlying exception "{1}".

Category:
Configuration

Cause:
The policy advertisement failed due to invalid tenant context.

Action:
Ensure that a valid tenant context is set in the header for the policy advertisement.

WSM-01600
error in creating or initializing the assertion, key={0}, qname={1}, wspqname={2}, constructorName={3}

Category:
Programmatic

Cause:
An assertion object could not be created.

Action:
Verify that the assertion follows the interface requirements defined in the Oracle documentation.

WSM-01601
failure in loading the resource

Category:
Configuration

Cause:
The requested resource could not be loaded.

Action:
Ensure that the requested resource is present in the class path.

WSM-01602
error in loading class {0}

Category:
Programmatic

Cause:
The requested class could not be loaded.

Action:
Ensure that the requested class is present in the class path.

WSM-01603
failure in parsing the policy due to {0}.

Category:
Data

Cause:
Parsing of the policy failed.

Action:
Ensure that the policy XML follows the policy schema, or a valid policy file exists.

WSM-01604
XML Parser Configuration error

Category:
Configuration

Cause:
The XML Parser was not configured properly.

Action:
Consult Oracle documentation or Java documentation on how to configure the XML Parser.

WSM-01605
XML parser exception

Category:
Data

Cause:
Parsing of the XML failed.

Action:
Ensure that the XML is well formed.

WSM-01606
system I/O error

Category:
Files

Cause:
The system could not open the Input/Output streams.

Action:
Consult the Java documentation.

WSM-01607
XPath expression evaluation error

Category:
Data

Cause:
Evaluation of the XPATH expression failed.

Action:
Ensure that the XPATH expression is valid, and the XML follows the schema.

WSM-01608
The class cannot be found.

Category:
Configuration

Cause:
The requested class was not found in the class path.

Action:
Ensure that the class name is correct in the configuration files and is in the class path.

WSM-01610
cannot initialize standard serializers/deserializers

Category:
Configuration

Cause:
The standard serializer and deserializer objects could not be loaded.

Action:
Ensure that the product configuration is correct. If the problem persists, contact Oracle Support Services.

WSM-01611
The class cannot be loaded because of Java security restrictions.

Category:
Configuration

Cause:
The requested classes could not be loaded due to class loading security restrictions.

Action:
Contact the site administrator or consult the Java documentation to ensure that the classes have the necessary Java security permissions.

WSM-01612
An instance of the requested class cannot be created.

Category:
Configuration

Cause:
The system could not create an instance of the requested class.

Action:
Consult the Java documentation or contact Oracle Support Services.

WSM-01613
The XML parser cannot be configured.

Category:
Configuration

Cause:
The XML parser could not be configured.

Action:
Consult the Java documentation on how to configure the XML parser.

WSM-01614
The assertion XML Java Document cannot be serialized to a String.

Category:
Data

Cause:
The assertion XML Java Document could not be serialized to a String.

Action:
Check the assertion for any errors and retry the operation.

WSM-01615
The assertion XML String cannot be converted to a Java object.

Category:
Data

Cause:
The assertion XML String could not converted to a Java Document.

Action:
Ensure that the String being converted to XML is a well-formed XML.

WSM-01616
Policy {0} cannot be inserted into the WSDL.

Category:
Data

Cause:
The WSDL extensions for the policy could not be found or were incorrectly configured.

Action:
Ensure that the WSDL extensions for the policy being injected are available and configured. Consult Oracle documentation for more information.

WSM-01617
error in parsing the policies embedded in the WSDL

Category:
Data

Cause:
The WSDL extensions for the policy could not be found or were incorrectly configured.

Action:
Ensure that the WSDL extensions for policy are available and configured. Consult Oracle documentation for more information.

WSM-01618
error in parsing the policy references embedded in the WSDL

Category:
Data

Cause:
The XML for the policy references in the WSDL could not be parsed.

Action:
Ensure that the WSDL extensions for the policy reference are available and configured. Consult Oracle documentation for more information.

WSM-01619
This assertion type is not recognized.

Category:
Data

Cause:
The assertion type was not recognized.

Action:
Consult Oracle documentation for the supported assertion types.

WSM-01620
cannot convert XML Java Document to String

Category:
Data

Cause:
The XML Java Document being converted was not well formed.

Action:
Ensure that the assertions can be serialized to a String.

WSM-01621
Policy intersection algorithm is not defined for assertion type :

Category:
Data

Cause:
The policy intersection algorithm was not found for the assertion.

Action:
Ensure that the intersection algorithm for the assertion used is configured.

WSM-01622
Policy merge algorithm is not defined for assertion type :

Category:
Data

Cause:
The policy merge algorithm was not found for the assertion.

Action:
Ensure that the merge algorithm for the assertion used is configured.

WSM-01623
Policy reference cannot be resolved :

Category:
Data

Cause:
The policy reference was invalid.

Action:
Ensure that the policy reference is valid.

WSM-01624
The policy does not exist in the policy store :

Category:
Data

Cause:
The policy reference was invalid, or the referenced policy could not be retrieved.

Action:
Ensure that the policy reference is valid, and the policy exists in the policy store.

WSM-01625
The Name attribute of the property is missing.

Category:
Data

Cause:
The Name attribute for a property was missing.

Action:
Provide a value for the Name attribute.

WSM-01626
The Type attribute of the property is missing.

Category:
Data

Cause:
The Type attribute for a property was missing.

Action:
Provide a value for the Type attribute.

WSM-01627
The assertion contains too many bindings.

Category:
Data

Cause:
The assertion contained more than one binding.

Action:
Ensure that the assertion contains a single binding.

WSM-01628
The policy normalization algorithm is not defined for this assertion type

Category:
Data

Cause:
The policy normalization algorithm was not found for the assertion.

Action:
Ensure that the normalization algorithm for the assertion used is configured.

WSM-01629
The assertion template contains too many assertions.

Category:
Data

Cause:
The assertion template contained more than one assertion.

Action:
Ensure that assertion template contains only one assertion.

WSM-01630
Element {0} is not a known policy element.

Category:
Data

Cause:
XML parsing failed; the system encountered unsupported XML elements.

Action:
Ensure that the XML follows the schema, and the XML contains only those elements that are supported.

WSM-01631
The assertion {0} contains multiple bindings.

Category:
Data

Cause:
The assertion contained more than one binding.

Action:
Ensure that the assertion contains only one binding.

WSM-01632
The assertion {0} contains multiple policies as child elements.

Category:
Data

Cause:
The assertion contained more than one policy child element.

Action:
Ensure that the assertion contains only one policy child element.

WSM-01633
Assertion type {0} does not match the corresponding Java Object type created.

Category:
Configuration

Cause:
The assertion type was incorrectly defined for the assertion.

Action:
Ensure that the correct assertion type is set for the assertion.

WSM-01635
Passed Java Object {0} does not extend the Assertion class

Category:
Data

Cause:
The Assertion class did not extend the correct classes.

Action:
Consult Oracle Documentation for creating assertion implementations.

WSM-01636
The assertion type {0} is not supported.

Category:
Data

Cause:
The assertion type does not match any of the predefined assertion types.

Action:
Ensure that the assertion type is supported.

WSM-01637
The policy attachment cannot be parsed.

Category:
Data

Cause:
The policy attachment XML was invalid.

Action:
Ensure that policy attachment XML follows the policy attachment XML schema.

WSM-01638
The policy attachment is not valid because the domain is not specified.

Category:
Data

Cause:
The policy attachment did not contain domain expressions.

Action:
Ensure that policy attachment XML follows the policy attachment XML schema.

WSM-01640
The policy reference {0} is not valid.

Category:
Data

Cause:
The policy reference could not be resolved.

Action:
Ensure that the referenced policy exists in the policy store.

WSM-01641
The policy advertisement level is not specified for the policy.

Category:
Configuration

Cause:
The policy advertisement level was not specified.

Action:
Ensure that a valid value is set for the policy advertisement level.

WSM-01642
Policy advertisement is not supported for unsupported WSDL elements.

Category:
Data

Cause:
Policy advertisement was not supported for the WSDL object.

Action:
Consult Oracle documentation for supported WSDL objects.

WSM-01643
What the XML system expects is different from what is encountered.

Category:
Data

Cause:
Usage of system was invalid or the feature was unsupported.

Action:
Consult Documentation on usage and supported features.

WSM-01644
The WSDL object {0} is not supported.

Category:
Data

Cause:
The WSDL object was not supported.

Action:
Consult Oracle documentation for the supported WSDL objects.

WSM-01645
The resource pattern {0} does not match the corresponding WSDL object.

Category:
Data

Cause:
WSDL Objects did not match.

Action:
Ensure that the WSDL Objects match.

WSM-01646
The value for the attachTo attribute of the policy is not valid.

Category:
Data

Cause:
The attachTo attribute of the policy did not match any of the predefined attachTo values.

Action:
Consult Oracle documentation for the valid values for the attachTo attribute.

WSM-01647
There are no policies that match the specified category {0} and resource pattern {1}.

Category:
Data

Cause:
No policies matched the specified search criteria.

Action:
Ensure that the policies that match the search categories exist in the policy store.

WSM-01650
cannot construct policy object

Category:
Programmatic

Cause:
Construction of the policy Java object failed.

Action:
Consult the diagnostic log for details.

WSM-01651
cannot advertise requested policies

Category:
Programmatic

Cause:
Advertisement of the policies failed.

Action:
Consult the diagnostic log for details, or contact Oracle Support Services.

WSM-01652
error in parsing the time stamp in the policy set document

Category:
Data

Cause:
The Timestamp attribute in the XML representation of a policy set document is not a valid number.

Action:
Correct or remove the invalid attribute value.

WSM-01653
The assertion contains more than one Guard element.

Category:
Data

Cause:
The assertion contained more than one guard.

Action:
Ensure that the assertion contains a single guard.

WSM-01654
failure in serialization of security scenario assertion

Category:
Data

Cause:
The SecurityScenario in OraPolicy could not be serialized or was incorrectly configured.

Action:
Ensure that the OraPolicy is correct. Consult Oracle documentation for more information.

WSM-01655
There are no policies that match the specified category {0}.

Category:
Data

Cause:
No policies matched the specified category.

Action:
Ensure that the policies that match the search category exist in the policy store.

WSM-01656
generic Oracle WSM Policy Manager error

Category:
Data

Cause:
An internal error occurred during the Policy related operation.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-01657
Oracle WSM Advertisement Engine must be initialized with valid properties. Following properties [{0}] are either empty or null

Category:
Configuration

Cause:
WSM Advertisement Engine initialized with invalid parameters.

Action:
Ensure that valid parameters are set during WSM Advertisement Engine configuration

WSM-01658
X509 Certificate will not be advertised as {0} not found

Category:
Other

Cause:
Implementation class for advertising X509 Certificate in WSDL is not available

Action:
Ensure that implementation class required for advertising X509 Certificate in WSDL is not available. Consult diagnostic log for details or contact Oracle Support Services.

WSM-01659
A JAXBContext cannot be created due to underlying exception "{0}".

Category:
Data

Cause:
One or more expected classes could not be located.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-01660
A JAXB unmarshaller cannot be created due to underlying exception "{0}".

Category:
Data

Cause:
An error occurred while creating an unmarshaller.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-01661
A string cannot be unmarshalled into an object due to underlying exception "{0}".

Category:
Data

Cause:
The string is not suitable for unmarshalling to the requested type.

Action:
Provide a string that is suitable for unmarshalling to the requested type.

WSM-01662
The QName "{0}" does not match the expected QName "{1}" for the unmarshalled object.

Category:
Data

Cause:
The string is not suitable for unmarshalling to the requested type.

Action:
Provide a string that is suitable for unmarshalling to the requested type.

WSM-01663
A null or empty string cannot be unmarshalled into an Intent object.

Category:
Data

Cause:
An attempt was made to unmarshall an Intent from a null or empty String.

Action:
Provide a String that contains a marshalled Intent.

WSM-01664
A null or empty string cannot be unmarshalled into a PolicySet object.

Category:
Data

Cause:
An attempt was made to unmarshall a PolicySet from a null or empty String.

Action:
Provide a String that contains a marshalled PolicySet.

WSM-01665
A JAXB marshaller cannot be created due to underlying exception "{0}".

Category:
Data

Cause:
An error occurred while creating a marshaller.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-01666
An object cannot be marshalled to a string due to underlying exception "{0}".

Category:
Data

Cause:
Marshalling the supplied type of the object is not supported.

Action:
Provide an object of a supported type.

WSM-01667
An object cannot be marshalled to a DOM object due to underlying exception "{0}".

Category:
Data

Cause:
Marshalling the supplied type of the object is not supported.

Action:
Provide an object of a supported type.

WSM-01668
A null Intent object cannot be marshalled.

Category:
Data

Cause:
An attempt was made to marshall a null Intent object.

Action:
Provide a non-null Intent object.

WSM-01669
A null PolicySet object cannot be marshalled.

Category:
Data

Cause:
An attempt was made to marshall a null PolicySet object.

Action:
Provide a non-null PolicySet object.

WSM-01670
An object cannot be marshalled into a null DOM object.

Category:
Data

Cause:
An attempt was made to marshall an object into a null Document object.

Action:
Provide a non-null Document object.

WSM-01671
The DOM element cannot be null for policy subject identified by the resource pattern: "{0}".

Category:
Compliance

Cause:
The null DOM element was passed.

Action:
Pass a valid non-null DOM element.

WSM-01672
The policy reference URI: "{1}" for policy subject identified by the resource pattern: "{0}" cannot be empty.

Category:
Compliance

Cause:
Empty policy references were found in the DOM element node.

Action:
Verify the DOM element node and make sure the policy references specify a valid value and the referenced policies exist in the repository.

WSM-01673
Duplicate policy references: "{1}" are found for policy subject identified by resource pattern "{0}".

Category:
Compliance

Cause:
Duplicate policy references were found in the same DOM element node.

Action:
Remove the duplicate policy references from the DOM element node.

WSM-01674
The DOM element: "{1}" for policy subject identified by resource pattern "{0}" is unsupported element.

Category:
Compliance

Cause:
Policies cannot be retrieved for unsupported DOM element node.

Action:
Verify that a supported DOM element node is provided for retrieving the policy.

WSM-01675
The policy references cannot be null.

Category:
Compliance

Cause:
A null policy reference was passed.

Action:
Pass the valid non-null policy reference object.

WSM-01676
The resource pattern cannot be null.

Category:
Compliance

Cause:
A null resource pattern was passed.

Action:
Pass a valid non-null resource pattern.

WSM-01677
The domain expression cannot be null.

Category:
Compliance

Cause:
A null domain expression was passed.

Action:
Pass a valid non-null domain expression.

WSM-01678
Element {0} is not a valid child element for Policy object.

Category:
Data

Cause:
Invalid child element found for Policy object.

Action:
Check the policy string being parsed and make sure only valid child elements are present for the Policy.

WSM-01679
A DOM node cannot be unmarshalled into an object due to underlying exception "{0}".

Category:
Data

Cause:
The string is not suitable for unmarshalling to the requested type.

Action:
Provide a string that is suitable for unmarshalling to the requested type.

WSM-01680
A null node cannot be unmarshalled into a RepositoryInfo object.

Category:
Data

Cause:
An attempt was made to unmarshall a RepositoryInfo from a null node.

Action:
Provide a node that contains a marshalled RepositoryInfo.

WSM-01681
A null or empty string cannot be unmarshalled into a RepositoryInfo object.

Category:
Data

Cause:
An attempt was made to unmarshall a RepositoryInfo from a null or empty String.

Action:
Provide a String that contains a marshalled RepositoryInfo.

WSM-01682
A null RepositoryInfo object cannot be marshalled.

Category:
Data

Cause:
An attempt was made to marshall a null RepositoryInfo object.

Action:
Provide a non-null RepositoryInfo object.

WSM-01683
The passed String "{0}" could not be parsed using UTF encoding.

Category:
Data

Cause:
Underlying JVM does not support UTF-8 encoding.

Action:
Check the JVM configuration to make sure it supports UTF-8 encoding format.

WSM-01684
A null or empty string cannot be unmarshalled into a Policy object.

Category:
Data

Cause:
An attempt was made to unmarshall a Policy from a null or empty String.

Action:
Provide a String that contains a marshalled Policy.

WSM-01685
Issuer Uri is not available. Either sts_trust_config_service_policy is not attached to service or the Issuer Uri is missing from the policy. Ignore this warning if sts_trust_config_client_policy is attached to client.

Category:
Configuration

Cause:
Issuer Uri is not available. Either sts_trust_config_service_policy is not attached to service or the Issuer Uri is missing from the policy. Ignore this warning if sts_trust_config_client_policy is attached to client.

Action:
Attach sts_trust_config_service_policy if not attached yet, or specify issuer uri value in the policy if not specified. Ignore if using sts_trust_config_client_policy.

WSM-01686
Advertisement failed due to an unexpected assertion type: {0}.

Category:
Configuration

Cause:
The assertion type is not recognized.

Action:
Internal error. Provide

WSM-01687
The constant property "{0}" cannot be overridden.

Category:
Configuration

Cause:
There is an attempt to override a property value which is defined as a constant in the policy.

Action:
Ensure that there is no attempt to override a constant property.

WSM-01688
X509 Certificate will not be advertised due to underlying exception "{0}".

Category:
Configuration

Cause:
Either the keystore was not available or the keystore configuration was incorrect.

Action:
Ensure the keystore exists and that the keystore password and aliases are correct.

WSM-01689
Advertisement failed due to an incorrect ws-policy/ws-securitypolicy specification version {0}/{1}.

Category:
Configuration

Cause:
Invalid ws-policy/ws-securitypolicy specification version used to advertise policy.

Action:
Ensure the ws-policy/ws-securitypolicy specification versions are correct.

WSM-01690
Assertion {0} located by QName {1} is not an instanceof type {2}.

Category:
Data

Cause:
An internal error, probably policy was not deserialized into the correct assertion instance.

Action:
Consult diagnostic log for details or contact Oracle Support Services.

WSM-01691
Cannot construct or access policy object for policy "{0}" due to underlying exception "{1}".

Category:
Programmatic

Cause:
Construction of the policy Java object failed for the given policy name.

Action:
Consult the diagnostic log for details.

WSM-01692
Advertisement failed due to multiple ws-policy specification version specified.

Category:
Configuration

Cause:
Multiple ws-policy specification version used to advertise policy.

Action:
Remove the duplicate ws-policy specification versions and try again.

WSM-01693
Advertisement failed due to multiple wssecurity-policy specification version specified.

Category:
Configuration

Cause:
Multiple ws-securitypolicy specification version used to advertise policy.

Action:
Remove the duplicate ws-securitypolicy specification versions and try again.

WSM-01694
Policy compatibility check failed due to invalid policy set. {0}.

Category:
Other

Cause:
Policy compatibility check failed due to invalid policy set.

Action:
Ensure that the policy set attached to the client is a valid policy set. Consult diagnostic log for details or contact Oracle Support Services.

WSM-01695
Encountered internal error while attempting to reorder PolicyReferences "{0}" in a PolicySet "{1}".

Category:
Other

Cause:
Encountered unexpected Policy model exception during reordering PolicyReferences in a PolicySet

Action:
Consult diagnostic log for details or contact Oracle Support Services.

WSM-01696
While validating the input PolicySet array to be merged, one or more PolicySets resource pattern are not same as that of the base, baseResourcePattern={0}, invalid input PolicySets={1}

Category:
Other

Cause:
While validating the input PolicySet array to be merged, found policyset resourcepattern that is different than that of the base.

Action:
Make sure ResourcePattern of all PolicySet in the array either all null, or for non-null ones they must all have the same ResourcePattern.

WSM-01697
The ResourcePattern of the base runtime PolicySet for merging is null, basePolicySet={0}, input PolicySet array={1}. All PolicySet in the array should be either null, or has the same resource pattern as that of the base policy set and all callback policy sets should have the same resource pattern.

Category:
Other

Cause:
The ResourcePattern of the base runtime Policy Set for merging is null, possibly the base runtime Policy Set is constructed using empty Policyset() constructor.

Action:
Make sure runtime PolicySet is created with not-null ResourcePattern.

WSM-01698
Runtime PolicySet is locked and it can not be modified with operation "{0}" and argument "{1}".

Category:
Other

Cause:
Runtime PolicySet is locked and read only; it cannot be modified

Action:
Donot modify PolicySet

WSM-01699
Runtime PolicySet "{0}" operation got an invalid argument "{1}" with value "{2}".

Category:
Other

Cause:
Runtime PolicySet add method passed in a null or invalid argment(s).

Action:
Check the arguments and correct them.

WSM-01700
The current Runtime PolicySet "{0}" merge method got an invalid PolicySet "{1}" in the List of PolicySet passed in; it is not an instance of PolicySet, very likely it is a CallbackPolicySet

Category:
Other

Cause:
Runtime PolicySet merge method passed invalid argument.

Action:
Check the arguments and correct them.

WSM-01701
Cannot perform changes to the DOM document provided to the storage provider since its a read-only document.

Category:
Other

Cause:
WSM Assembly document could not be fetched for write operation.

Action:
The WSM Assembly document provided to the storage provider does not support update. Provide a writeable DOM document and retry the operation.

WSM-01702
A null WSM Assembly object cannot be marshalled.

Category:
Other

Cause:
An attempt was made to marshall a null WsmAssembly object.

Action:
Provide a non-null WsmAssembly object.

WSM-01703
Failed to retrieve descriptor identified by "{0}" in storage provider due to an exception

Category:
Other

Cause:
WSM descriptor document could not be fetched due to IOException.

Action:
Check with logging for detail, and retry, if problem persists, contact Oracle Support.

WSM-01704
While advertising policies under subject "{0}", the specified web service with QName "{1}" does not exist in the wsdl; it may not be valid, make sure that namespace and local name of the service are correct.

Category:
Other

Cause:
The QName of the web service specified does not exist in the wsdl

Action:
Verify the namespace and local name and make sure there are valid

WSM-01705
While advertising policies under subject "{0}", the specified port name "{1}" does not exist under the service "{2}" in wsdl.

Category:
Other

Cause:
The port name specified does not exist in the servie of wsdl

Action:
Verify the port name and make sure it is valid

WSM-01706
A null node cannot be unmarshalled into an Intent object.

Category:
Data

Cause:
An attempt was made to unmarshall an intent from a null node.

Action:
Provide a node that contains a marshalled intent.

WSM-01707
A null node cannot be unmarshalled into an assertion metadata object.

Category:
Data

Cause:
An attempt was made to unmarshall assertion metadata from a null node.

Action:
Provide a node that contains a marshalled assertion metadata.

WSM-01708
Advertisement expression "{0}" for portable expression "{1}" is not valid.

Category:
Data

Cause:
The advertisment expression probably is not set correctly.

Action:
Check the log and verify it is not null and confirm to the format.

WSM-01709
The Runtime PolicySet cannot be advertised due to validation errors. PolicySet "{0}" validation errors: "{1}" .

Category:
Other

Cause:
Runtime PolicySet cannot be advertised due to validation errors.

Action:
Check the logs and correct errors in the PolicySet.

WSM-01710
The Policy "{0}" has following validation errors= "{1}".

Category:
Other

Cause:
Policy has validation errors.

Action:
Check the logs and correct errors in the Policy.

WSM-01711
One or more Callback PolicySets ResourcePattern are not the same. baseResourcePattern={0}, callbackPolicySetsHaveDifferentResourcePatterns= {1}. All PolicySet in the array should be either null, or has the same resource pattern as that of the base policy set and all callback policy sets should have the same resource pattern.

Category:
Other

Cause:
Found invalid PolicySet in the input PolicySet array to be merged.

Action:
Make sure all PolicySet resource pattern in the array should be either null, or has the same resource pattern as that of the base policy set and all callback policy sets should have the same resource pattern.

WSM-01712
While validating the input PolicySet array to be merged, input resource pattern subject type={0} is incompatible with that of base={1}, input policySet={2}.

Category:
Other

Cause:
While validating the input PolicySet array to be merged, input callback subject type is not compatible with that of the base.

Action:
Input resource pattern should be either null, same as base, or a compatible callback type

WSM-01713
A null node cannot be unmarshalled into a TimestampInfo object.

Category:
Data

Cause:
An attempt was made to unmarshall a TimestampInfo from a null node.

Action:
Check the log and retry the operation.

WSM-01714
A null TimestampInfo object cannot be marshalled.

Category:
Data

Cause:
An attempt was made to marshall a null TimestampInfo object.

Action:
Check the log and retry the operation.

WSM-01715
The current thread context class loaders "{0}" are unable to locate the OWSM seed policy JAR "{1}". URLs that have the searched resource "{2}" are "{3}".

Category:
Configuration

Cause:
The current thread classpath does not include the path to the wsm-seed-policies.jar.

Action:
Check the log for detail info.

WSM-01716
The current thread context class loader is unable to locate the OWSM seed policy JAR "{0}" by searching resource "{1}".

Category:
Configuration

Cause:
The current thread classpath does not include the path to the wsm-seed-policies.jar.

Action:
Check the log and retry the operation.

WSM-01717
A null node cannot be unmarshalled into an PolicyReference object.

Category:
Data

Cause:
An attempt was made to unmarshal PolicyReference from a null node.

Action:
Provide a node that contains a valid policy reference.

WSM-01718
A null PolicyReference object cannot be marshalled.

Category:
Data

Cause:
An attempt was made to marshal a null PolicyReference object.

Action:
Provide a non-null PolicyReference object.

WSM-01719
Error while getting input stream for entry "{0}" from seed jar located at "{1}".

Category:
Data

Cause:
Error in reading jar entry from seed jar.

Action:
Check the jar file and retry the operation.

WSM-01720
Error while parsing entry "{0}" from seed jar located at "{1}".

Category:
Data

Cause:
Error in parsing file in seed jar.

Action:
Remove the invalid file and retry the operation.

WSM-01751
The name of an assertion property is empty.

Category:
Data

Cause:
The name of an assertion property was empty.

Action:
Make sure that you specify a name for all assertion properties.

WSM-01752
The data type of the value does not match the data type of property {0}. The expected data type is "string".

Category:
Data

Cause:
The datatype of the property value entered was not of type "string".

Action:
Make sure that the data type for the property value is of type "string".

WSM-01753
The data type of the value does not match the data type of property {0}. The expected data type is "boolean".

Category:
Data

Cause:
The data type of the property value entered was not of type "boolean".

Action:
Make sure that the data type for the property value is of type "boolean".

WSM-01754
The data type of the value does not match the data type of property {0}. The expected data type is "integer".

Category:
Data

Cause:
The data type of the property value entered was not of type "integer".

Action:
Make sure that the data type for the property value is of type "integer".

WSM-01755
An empty value is specified for property {0}.

Category:
Data

Cause:
An empty value was specified for a property that has a data type of type "password".

Action:
Specify a value for all properties that have a data type of type "password".

WSM-01756
The Property Set name field of context: {0} is empty

Category:
Data

Cause:
The Property Set Name field in one of the assertions was empty.

Action:
Make sure that you specify a name for all assertion property sets.

WSM-01757
The name attribute for the "Config" element is empty.

Category:
Data

Cause:
The name for the Config element was empty.

Action:
Make sure that a name is specified for the Config element.

WSM-01758
The assertion name is empty.

Category:
Data

Cause:
The assertion name was empty.

Action:
Make sure that the assertion name is specified.

WSM-01759
The policy ID is empty.

Category:
Data

Cause:
The policy ID was empty.

Action:
Make sure that the policy ID is specified.

WSM-01760
The policy name is empty.

Category:
Data

Cause:
The policy name was empty.

Action:
Make sure that the policy name is specified.

WSM-01761
Specifying a policy ID for a child policy is not permitted : {0}.

Category:
Data

Cause:
Policy ID must not be specified for child policies.

Action:
Remove the policy ID of the child policy.

WSM-01762
Specifying a policy name for a child policy is not permitted : {0}.

Category:
Data

Cause:
Policy name must not be specified for child policies.

Action:
Remove the policy name of the child policy.

WSM-01763
The value specified for the policy attachTo attribute {0}, does not match any of the supported values.

Category:
Data

Cause:
The value specified for the policy attachTo attribute did not match any of the supported values.

Action:
Specify a valid value for the attachTo attribute. Consult the Oracle documentation for the supported values.

WSM-01764
The value specified for the policy category {0} does not match any of the supported values.

Category:
Data

Cause:
The value specified for policy category attribute did not match any of the supported values.

Action:
Specify a valid value for the category attribute. Consult the Oracle documentation for the supported values.

WSM-01765
The data type of the value specified for property {0} is not supported.

Category:
Data

Cause:
The data type specified for the property did not match any of the supported data types.

Action:
Specify a valid data type for the property. Consult the Oracle documentation for the supported data types.

WSM-01766
The assertion template ID cannot be empty.

Category:
Data

Cause:
The assertion template ID was empty.

Action:
Specify a value for assertion template ID.

WSM-01767
The assertion template name cannot be empty.

Category:
Data

Cause:
The assertion template name was empty.

Action:
Specify a value for the assertion template name.

WSM-01768
The value specified for the assertion template attachTo attribute {0} does not match any of the supported values.

Category:
Data

Cause:
The value specified for the assertion template attachTo attribute did not match any of the supported values.

Action:
Specify a valid value for the attachTo attribute. Consult the Oracle documentation for the supported values.

WSM-01769
The value specified for the assertion template category {0} does not match any of the supported values.

Category:
Data

Cause:
The value specified for the assertion template category attribute did not match any of the supported values.

Action:
Specify a valid value for the category attribute. Consult the Oracle documentation for the supported values.

WSM-01770
A value or default value is not specified for property {0}.

Category:
Data

Cause:
No value or default value was specified for the property.

Action:
Specify a value or a default value for the property.

WSM-01771
Attaching multiple reliable messaging policies is not supported. Only one reliable messaging policy can be attached to a policy subject

Category:
Data

Cause:
More than one reliable messaging policy was attached to a policy subject.

Action:
Make sure that only one reliable messaging policy is attached to a policy subject.

WSM-01772
Attaching multiple make connection(WSMC) policies is not supported. Only one WSMC policy can be attached to a policy subject.

Category:
Data

Cause:
More than one MTOM policy was attached to a policy subject.

Action:
Make sure that only one reliable MTOM is attached to a policy subject.

WSM-01773
Attaching multiple WS-Addressing policies is not supported. Only one WS-Addressing policy can be attached to a policy subject.

Category:
Data

Cause:
The user attached more than one WS-Addressing policy.

Action:
Make sure that only one reliable WS-Addressing is attached to a policy subject.

WSM-01774
The policy "{0}" cannot be attached to policy subject "{1}" having unsupported subject type "{2}".

Category:
Data

Cause:
A policy was attached to an unsupported policy subject.

Action:
Make sure that the policy subject supports policy attachment. Consult the Oracle documentation for the supported values.

WSM-01775
The policy "{0}" cannot be attached to ResourcePattern "{1}" SubjectType "{2}" of attachTo "{3}" since it may only be used with "{4}".

Category:
Data

Cause:
An incompatible policy was attached to the policy subject.

Action:
Make sure that the attached policy is compatible with the policy subject.

WSM-01776
The policy reference "{0}" is invalid.

Category:
Data

Cause:
The policy reference was invalid because the policy did not exist.

Action:
Make sure that the referenced policy exists in the policy store.

WSM-01777
Attaching multiple authorization security policies is not supported. Only one authorization security policy can be attached to a policy subject.

Category:
Data

Cause:
More than one authorization security policy was attached to a policy subject.

Action:
Make sure that only one authorization security policy is attached to a policy subject.

WSM-01778
Attaching multiple authentication security policies is not supported. Only one authentication security policy can be attached to a policy subject.

Category:
Data

Cause:
More than one authentication security policy was attached to a policy subject.

Action:
Make sure that only one authentication security policy is attached to a policy subject.

WSM-01779
Attaching multiple message protection security policies is not supported. Only one message protection security policy can be attached to a policy subject.

Category:
Data

Cause:
More than one message protection security policy was attached to a policy subject.

Action:
Make sure that only one message protection security policy is attached to a policy subject.

WSM-01780
The policy reference category and the policy category do not match.

Category:
Data

Cause:
There was a mismatch between the policy reference category and the policy category.

Action:
Ensure that the policy reference category matches the policy category.

WSM-01781
Validation failure due to generic error.

Category:
Data

Cause:
A generic internal error occurred.

Action:
Consult the diagnostic logs for details.

WSM-01782
Policy contains no assertions. A policy must contain at least one assertion.

Category:
Data

Cause:
The policy did not contain any assertions.

Action:
Make sure that the policy contains at least one assertion.

WSM-01783
Guard does not contain any of the three elements of resource-match, action-match and constraint-match.

Category:
Data

Cause:
Guard does not contain any of the three elments of resource-match, action-match and constraint-match.

Action:
Make sure that at least one of three elements of resource-match, action-match and constraint-match is specified with its corresponding value in the Guard element.

WSM-01784
Validation is not supported for "{0}" type of Documents. Only a Policy, AssertionTemplate or PolicySet can be validated.

Category:
Data

Cause:
Validation is not supported for the type of Documents.

Action:
Ensure that the document is either a Policy or a PolicySet or AssertionTemplate.

WSM-01785
Signing or encryption of the soap fault is not supported.

Category:
Data

Cause:
The soap fault is to be signed or encrypted.

Action:
Make sure that the soap fault is not to be signed or encrypted.

WSM-01786
Attaching multiple STS-Config policies is not supported. Only one STS-Config policy can be attached to a policy subject.

Category:
Data

Cause:
More than one sts-config policy was attached to a policy subject.

Action:
Make sure that only one sts-config policy is attached to a policy subject.

WSM-01787
The policy name {0} contains invalid characters.

Category:
Data

Cause:
The policy name contains invalid characters.

Action:
Make sure that policy name contains valid characters.

WSM-01788
The assertion template name {0} contains invalid characters.

Category:
Data

Cause:
The assertion template name contains invalid characters.

Action:
Specify a valid value for the assertion template name.

WSM-01789
Attaching multiple web service transaction(WSTX) policies is not supported. Only one WSTX policy can be attached to a policy subject.

Category:
Data

Cause:
More than one WSMC policy was attached to a policy subject.

Action:
Make sure that only one make connection policy is attached to a policy subject.

WSM-01790
Attaching multiple Message Transmission Optimization Mechanism (MTOM) policies is not supported. Only one MTOM policy can be attached to a policy subject.

Category:
Data

Cause:
More than one WSTX policy was attached to a policy subject.

Action:
Make sure that only one reliable WSTX is attached to a policy subject.

WSM-01791
Combination of a sts-config policy and a non sts authentication/message protection policy is not valid.

Category:
Data

Cause:
sts-config policy and non sts policy was attached to a policy subject.

Action:
Make sure that a sts-config policy and a non sts config policy are not attached together to a policy subject.

WSM-01792
Attachment of a sts-config policy without any sts policy is invalid. Attach a valid sts policy together with a sts-config policy.

Category:
Data

Cause:
Sts policy was attached without sts-config policy to a policy subject.

Action:
Make sure that a sts config policy is attached together with a sts policy to a policy subject.

WSM-01793
The OR group contains no assertions. Edit the OR group to include one or more assertions.

Category:
Data

Cause:
The OR group contains no assertions.

Action:
Edit the OR group to include one or more assertions.

WSM-01794
Combination of an oauth2-config policy and a non oauth2 client policy is not valid.

Category:
Data

Cause:
oauth2-config policy and non oauth2 policy was attached to a policy subject.

Action:
Make sure that an oauth2-config policy and a non oauth2 config policy are not attached together to a policy subject.

WSM-01795
Attachment of an oauth2 config policy without any oauth2 client policy is invalid. Ensure you attach a valid oauth2 policy either via Direct Policy Attachment or via Global Policy Attachment along with an oauth2 config policy.

Category:
Data

Cause:
Oauth2 config policy was attached without oauth2 client policy to a policy subject.

Action:
Make sure that an oauth2 config policy is attached together with a oauth2 policy to a policy subject.

WSM-01796
Attaching multiple Oauth2-Config policies is not supported. Only one Oauth2-Config policy can be attached to a policy subject.

Category:
Data

Cause:
More than one oauth2-config policy was attached to a policy subject.

Action:
Make sure that only one oauth2-config policy is attached to a policy subject.

WSM-01797
Attachment of an oauth2 client policy without oauth2 config policy is invalid. Ensure you attach a valid oauth2 config policy either via Direct Policy Attachment or via Global Policy Attachment along with an oauth2 client policy.

Category:
Data

Cause:
Oauth2 client policy was attached without oauth2-config policy to a policy subject.

Action:
Make sure that a oauth2 config policy is attached together with a oauth2 policy to a policy subject.

WSM-01801
The type of resources expression is empty or missing.

Category:
Data

Cause:
The value specified for the appliesTo attribute was empty.

Action:
Specify a valid non-empty value for the appliesTo attribute.

WSM-01802
The type of resources expression "{0}" is not supported.

Category:
Data

Cause:
The value specified for the appliesTo attribute was invalid.

Action:
Specify a valid value for the appliesTo attribute.

WSM-01811
The attachment expression is empty or missing; a non-empty expression with a function is expected.

Category:
Data

Cause:
The value specified for the attachTo attribute was empty.

Action:
Specify a valid, non-empty value for the attachTo attribute.

WSM-01812
The function "{2}" at index {1} in attachment expression "{0}" is empty or malformed. A function requires a non-empty, quoted value.

Category:
Data

Cause:
The argument for a function was missing, empty, or malformed.

Action:
Specify a valid, non-empty value for the function argument.

WSM-01813
The function "{2}" at index {1} in attachment expression "{0}" duplicates a previous function. A function may only appear once in an expression.

Category:
Data

Cause:
A function appeared more than once in an attachment expression.

Action:
Remove the duplicated function from the expression.

WSM-01814
The function "{2}" is not expected at index {1} in attachment expression "{0}". An operator is expected at this point.

Category:
Data

Cause:
A function was found in an attachment expression where an operator was expected.

Action:
Specify the "and" operator between each function.

WSM-01815
A function is expected at index {1} in attachment expression "{0}".

Category:
Data

Cause:
The attachment expression ended with an operator.

Action:
Remove the dangling operator or add the missing function.

WSM-01816
The operator "{2}" at index {1} in attachment expression "{0}" is not supported. "and" is the only supported operator.

Category:
Data

Cause:
An unrecognized operator was found in an attachment expression.

Action:
Specify the "and" operator between each function.

WSM-01817
The text "{2}" at index {1} in attachment expression "{0}" is not expected. A function is expected at this point.

Category:
Data

Cause:
An unrecognized block of text was found in an attachment expression where a function was expected.

Action:
Specify a valid function in the expression.

WSM-01818
The text "{2}" at index {1} in attachment expression "{0}" is unrecognized. The operator "and" is expected at this point.

Category:
Data

Cause:
An unrecognized block of text was found in an attachment expression where an operator was expected.

Action:
Specify the "and" operator between each function.

WSM-01821
The function "{0}" in attachment expression "{1}" is incompatible with "{2}" type of resources.

Category:
Data

Cause:
A function was found in an attachment expression that is not usable with the type of resource.

Action:
Specify a function that is compatible with the associated type of resource.

WSM-01822
The function "{0}" in attachment expression "{1}" is not supported for attachment.

Category:
Data

Cause:
A function was found in an attachment expression that is not usable for attachment.

Action:
Specify a function that is compatible with the associated type of resource.

WSM-01823
The policy set name is empty.

Category:
Data

Cause:
The policy set name was empty.

Action:
Make sure that the policy set name is specified.

WSM-01824
The policy set name {0} contains invalid characters.

Category:
Data

Cause:
The policy set name contains invalid characters.

Action:
Make sure that policy set name contains valid characters.

WSM-01825
Secure conversation is enabled in assertion to which it does not currently apply.

Category:
Data

Cause:
Secure conversation is enabled in assertion to which it does not currently apply.

Action:
Make sure that secure conversation is enabled only in supported assertions.

WSM-01826
Secure conversation re-authenticate feature is not supported in this assertion.

Category:
Data

Cause:
Secure conversation re-authenticate feature is not supported in this assertion.

Action:
Make sure that secure conversation re-authenticate feature is enabled only in supported assertions.

WSM-01827
Attaching multiple policies of category "{0}" is not supported. Policies in list ["{1}"] already have the category, current policy "{2}" also has that category.

Category:
Data

Cause:
More than one policy with the same category was attached to a policy subject.

Action:
Make sure that only one such policy is attached to a policy subject.

WSM-01828
Invalid category : {0} for policy : {1}. Only policies assigned to the security category are supported.

Category:
Compliance

Cause:
The Policy category provided was not valid.

Action:
Verify that the Policy category is correct.

WSM-01829
Policy: {0} contains unsupported assertions.

Category:
Security

Cause:
Policy contains unsupported assertions. Assertions of type http-security are not supported for WLS JAXWS web services.

Action:
Check the assertion type.

WSM-01830
The policy binding value "{0}" is not valid.

Category:
Security

Cause:
The policy binding value provided for the PolicySubject is invalid.

Action:
Verify that the SubjectType arguemt is correct.

WSM-01831
PII assertions cannot be combined with other assertions in a policy. This policy includes PII and non PII assertions which is not valid.

Category:
Configuration

Cause:
The policy contains PII assertion as well as other assertions. PII Assertion cannot be combined with other assertions in a policy.

Action:
Remove other assertions from this policy or remove the PII assertion.

WSM-01832
PII Policy {0} is not supported on the Resource {1} , as the PII policy is not supported on SubjectType : {2}

Category:
Configuration

Cause:
The PII Policy is not applicable on this SubjectType.

Action:
Detach the PII policy from the Subject.

WSM-01833
PII Policy {0} has local optimization turned ON, it should always be turned OFF.

Category:
Security

Cause:
Local optimization cannot be ON for PII Policy.

Action:
Turn local optimization off in PII policy.

WSM-01834
Policy: {0} contains assertion(s) that are not supported for the REST endpoint with Resource Pattern: {1}

Category:
Security

Cause:
Policy Set validation failed because the attached policy contains assertions that are not supported for REST endpoints.

Action:
Make sure the assertion(s) included in the policy are supported for REST endpoints.

WSM-01835
Policy: {0} contains assertion(s) that are not supported for the virtual endpoint with Resource Pattern: {1}, Subject type: {2}. If SubjectType is VS_SERVICE, policy must have VS_SERVICE intent and policy references must have SOAP_HTTP intent. If SubjectType is VS_REST_RESOURCE, policy must have VS_REST_RESOURCE intent and policy

references must have REST_HTTP intent. If SubjectType is VS_URL_RESOURCE, policy must have VS_URL_RESOURCE intent and policy references must have URL intent.

Category:
Security

Cause:
Policy Set validation failed because the attached policy contains assertions that are not supported for virtual endpoints.

Action:
Make sure the assertion(s) included in the policy are supported for virtual endpoints. Check log for more details.

WSM-01844
The data type of the value does not match the data type of property {0}. The expected data type is "long".

Category:
Data

Cause:
The data type of the property value entered was not of type "long".

Action:
Make sure that the data type for the property value is of type "long".

WSM-01845
The value specified for the policy attachTo attribute {0}, is invalid for the assertion category: {1}.

Category:
Data

Cause:
The value specified for the policy attachTo attribute is invalid for the category.

Action:
Specify a valid value for the attachTo attribute. Consult the Oracle documentation for the supported values.

WSM-01846
The policy "{0}" having category "{1}" is not valid for resource pattern "{2}" of subject type "{3}".

Category:
Security

Cause:
Policy of this category is not applicable to the subject type.

Action:
Detach the policy from the subject.

WSM-01847
The type of policy set "{0}" is not specified or empty.

Category:
Data

Cause:
The policy set type is not specified or empty.

Action:
Make sure that the policy set type is specified.

WSM-01848
The type "{0}" of PolicySet "{1}" is invalid

Category:
Data

Cause:
The value specified for the policy set type is invalid.

Action:
Specify a valid value for policy set type. Refer documentation for the list of valid values.

WSM-01849
The type "{0}" of PolicySet "{1}" does not support external attachments.

Category:
Data

Cause:
The external attachment is not spoorted by the specified subject type.

Action:
Specify subject type which supports external attachment.

WSM-01850
WARNING: Non-Security policies do not apply to {0}

Category:
Data

Cause:
Non-Security policies do not apply to resource type.

Action:
Make correction according to the documentation and retry.

WSM-01851
The policy "{0}" is not supported for SOAP/JMS endpoint.

Category:
Data

Cause:
Specified policy is not supported for SOAP JMS.

Action:
Make correction according to the documentation and retry.

WSM-01852
The field "{0}" of policyset "{1}" is not updatable; attampted to change {2} to "{3}".

Category:
Data

Cause:
Policyset field is not updatable.

Action:
Do not change the value of the field.

WSM-01853
The status field of object "{0}" has invalid value "{1}".

Category:
Data

Cause:
The value specified for status is invalid.

Action:
Specify a valid value for status. Refer documentation for the list of valid values.

WSM-01854
The constraint value "{0}" of PolicySet "{1}" is invalid and caused ParseException.

Category:
Data

Cause:
Parsing of constraint set in the global PolicySet caused ParseException

Action:
Correct the value of constraint in global PolicySet and retry.

WSM-01860
The configuration property name "{0}" is unknown.

Category:
Data

Cause:
The configuration property name is unknown.

Action:
Check the documentation and provide a valid name.

WSM-01861
The configuration property category "{0}" unknown.

Category:
Data

Cause:
The configuration property category is invalid.

Action:
Check the documentation and provide a valid category.

WSM-01862
The combination of property name "{0}" and category "{1}" is invalid.

Category:
Data

Cause:
The combination of property name and category is invalid.

Action:
Check the documentation and provide a valid combination of property name and category.

WSM-01863
Property "{0}" within category "{1}" is readonly and cannot be modified.

Category:
Data

Cause:
Read-only property cannot be modified.

Action:
Specify a modifiable property.

WSM-01864
Multiple values are not allowed for property "{0}" within category "{1}"

Category:
Data

Cause:
Multiple values are not allowed for the property.

Action:
Specify a single value.

WSM-01865
The format for value(s) "{0}" does not match the allowed format "{1}".

Category:
Data

Cause:
Format of the value does not match the allowed format.

Action:
Check the documentation and provide a valid format.

WSM-01866
The provided configuration platform type "{0}" contains invalid character.

Category:
Data

Cause:
The configuration platform type contains invalid character.

Action:
Please check the documentation and provide a valid platform type.

WSM-01867
The provided configuration domain name "{0}" contains invalid character.

Category:
Data

Cause:
The configuration domain name contains invalid character.

Action:
Please check the documentation and provide a valid domain name.

WSM-01868
Seed token issuer trust document "{0}" can not be modified or deleted. It is a read-only document.

Category:
Data

Cause:
The Seed Token Issuer Trust Document is read-only and can not be modified or deleted.

Action:
Create a new document that can be customized to your needs.

WSM-01869
A token issuer trust document name must be provided for this operation.

Category:
Data

Cause:
A token issuer trust document name is required for this operation.

Action:
Specify a name to proceed with this operation.

WSM-01870
The field "{0}" of Token Issuer Trust "{1}" is not updatable; attampted to change "{2}" to "{3}".

Category:
Data

Cause:
Trust field is not updatable.

Action:
Do not change the value of the field.

WSM-01871
The TokenIssuerTrust document name cannot be null or empty.

Category:
Security

Cause:
The TokenIssuerTrust document name cannot be null or empty.

Action:
Make sure the name is provided when creating an Issuer.

WSM-01872
The tokentype attribute "{0}" for the Issuer "{1}" is not supported.

Category:
Security

Cause:
The tokentype attribute for the Issuer is not supported.

Action:
Change it to a supported token type when creating the Issuer in token issuer trust document.

WSM-01873
The field "{0}" of an Issuer cannot be missing.

Category:
Security

Cause:
The issuer name cannot be null or empty.

Action:
Make sure the name is provided when creating an Issuer.

WSM-01874
The field "{0}" of Issuer is not updatable.

Category:
Data

Cause:
Trust field is not updatable.

Action:
Do not change the value of the field.

WSM-01875
The value of field "{0}" of Issuer is not valid, it must be a boolean value.

Category:
Security

Cause:
The enabled field should be a boolean value.

Action:
Make sure to use "true" or "false" boolean value.

WSM-01876
RelyingParty is only valid for Issuers that of JWT token type. Current Issuer token type is . "{0}".

Category:
Security

Cause:
The replying party is only valid for Issuers that are of JWT token type.

Action:
Change it to a supported tokentype vs relying party type pair when creating replying party under an Issuer.

WSM-01877
The value of field "{0}" in TokenIssuerTrust is not supported.

Category:
Security

Cause:
The field value in TokenIssuerTrust is not supported.

Action:
Change it to a supported key value type when creating the trusted key under an Issuer.

WSM-01878
KeyIdentifiers that are of publickey type are not accepted through user input but are resolved from metadata url "{0}".

Category:
Security

Cause:
The public key is not accepted through user input

Action:
Remove public KeyIdentifiers from user input data.

WSM-01879
The value of field "{0}" of the TrustedKey is not valid, it must be a boolean value.

Category:
Security

Cause:
The enabled field should be a boolean value.

Action:
Make sure to use "true" or "false" boolean value.

WSM-01880
The combination of value of field "{0}" and field "{1}" of TrustedKey is not supported.

Category:
Security

Cause:
The key and key value type combination is not valid

Action:
Change it to a supported key and key value type pair when creating the trusted key under an Issuer.

WSM-01881
The value of field "{0}" of TrustedKey is not valid for value of field "{1}" in Issuer.

Category:
Security

Cause:
The key type and its beloning Issuer's token type combination is not valid

Action:
Change it to a supported key type when creating the trusted key under an Issuer.

WSM-01882
The metadata URL "{0}" for fetching public key is not valid URL.

Category:
Security

Cause:
The TrustedKey MDRUL is not valid URL.

Action:
Provide a valid URL.

WSM-01883
Field "{0}" must be set.

Category:
Security

Cause:
The TrustedKey MDRUL should not be null.

Action:
Provide a valid URL value.

WSM-01884
Refresh interval "{0}" of TrustedKey is not valid; it should be an integer.

Category:
Security

Cause:
The TrustedKey refreshinterval is not an integer.

Action:
Provide an integer value.

WSM-01885
The field "{0}" in TrustedKey is applicable only and must be set for Issuers that are of JWT token type, current issuer token type is "{1}".

Category:
Security

Cause:
The TrustedKey MDRUL is applicable for issers of JWT token type.

Action:
Choose Issuer that is of JWT token type.

WSM-01886
The field "{0}" and "{1}" of a TokenAttributeRule cannot be empty, missing or NONE at the same time.

Category:
Security

Cause:
The TokenAttributeRule field cannot be null or empty at the same time.

Action:
Make sure the fields are provided when creating a TokenAttributeRule.

WSM-01887
The field "{0}" of TokenAttributeRule is not updatable.

Category:
Data

Cause:
TokenAttributeRule field is not updatable.

Action:
Do not change the value of the field.

WSM-01888
The field "{0}" of an Attribute is not updatable.

Category:
Data

Cause:
Attribute field is not updatable.

Action:
Do not change the value of the field.

WSM-01889
The field "{0}" of an Attribute cannot be missing.

Category:
Security

Cause:
The Attribute field cannot be null or empty.

Action:
Make sure the field is provided when creating an Attribute.

WSM-01890
The field "{0}" of the VirtualUser is not updatable.

Category:
Data

Cause:
VirtualUser field is not updatable.

Action:
Do not change the value of the field.

WSM-01891
The value of field "{0}" of the VirtualUser is not valid, it must be a boolean value.

Category:
Security

Cause:
The enabled field of VirtualUser should be a boolean value.

Action:
Make sure to use "true" or "false" boolean value.

WSM-01892
One or more values of field "{0}" in the VirtualUser is not valid.

Category:
Security

Cause:
One or more values in the a filed of a VritualUser is not valid.

Action:
Make a correction and try again.

WSM-01893
The value of field "{0}" of a TokenRoleMapping should not be null or empty

Category:
Security

Cause:
The field of a TokenRoleMapping should not have null or empty value.

Action:
Provid a non empty generic name.

WSM-01894
The value of field "{0}" of TokenRoleMapping should be an non empty list.

Category:
Security

Cause:
The field of TokenRoleMapping should not have null or empty list.

Action:
Provid a list of values.

WSM-01895
The value of field "{0}" of an Attribute or NameId should not be null or empty

Category:
Security

Cause:
The field of an Attribute or NameId should not have null or empty value.

Action:
Provid a non empty generic name.

WSM-01896
The value of field "{0}" of Mapping should not be null or empty

Category:
Security

Cause:
The field of an Mapping should not have null or empty value.

Action:
Provid a non empty generic name.

WSM-01897
ConfigOverride field "{0}" is either missing or has null or empty value

Category:
Security

Cause:
The field of ConfigOverride have either null or empty value.

Action:
Provid a generic name or value.

WSM-01898
The value of "{0}" contains invalid NCName character

Category:
Data

Cause:
Name contains invalid character.

Action:
Please check the documentation and provide valid name.

WSM-01899
The value of fields "{0}" of DiscoveryInfo must be set.

Category:
Data

Cause:
Required fields are null.

Action:
Provide valid value.

WSM-01900
Field "{0}" value of "{1}" is not a valid URL

Category:
Data

Cause:
Field value is not a valid URI.

Action:
Provide valid value.

WSM-01901
Field "{0}" value of "{1}" is not a valid PATH

Category:
Data

Cause:
Field value is not a valid URI.

Action:
Provide valid value.

WSM-01902
The value of one or more required fields "{0}" of Proxy are either empty or missing.

Category:
Data

Cause:
Required fields are missing.

Action:
Provide valid value.

WSM-01903
The proxyport value "{0}" of the Proxy is not an integer.

Category:
Data

Cause:
Port is not an integer.

Action:
Provide integer value.

WSM-01904
The field "{0}" of Proxy cannot be set to null

Category:
Data

Cause:
Field cannot be set to null.

Action:
Provide a valid value.

WSM-01905
The field "{0}" has invalid value, must be one of the predefinded values: {1}

Category:
Security

Cause:
The TrustedKey trust type is not one of the valid predefined values.

Action:
Provide a valid trust type.

WSM-03001
Oracle WSM Monitor internal error {0}

Category:
Configuration

Cause:
An unexpected error occurred while monitoring Oracle WSM Agent.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-03002
Failure initializing Oracle WSM Monitor, {0} is null.

Category:
Configuration

Cause:
Creation of one or more DMS Event sensors failed while initializing Oracle WSM Monitor.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-03003
The topology node value {0} is not valid.

Category:
Configuration

Cause:
The topology node value passed from the security interceptor to Oracle WSM Agent was invalid.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-03004
The parameter {0} is not valid.

Category:
Configuration

Cause:
The parameter was either null or invalid.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-04501
generic error in accessing the data store

Category:
Data

Cause:
An internal error occurred while accessing the MDS data store.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-04502
The name of the resource is empty.

Category:
Programmatic

Cause:
The name of the resource to be updated or retrieved was empty.

Action:
Assign a name to the resource being processed.

WSM-04503
resource {0} does not exist in the data store

Category:
Data

Cause:
The requested resource was not found in the data store.

Action:
Check the search criteria and try again.

WSM-04504
resource {0} cannot be updated

Category:
Data

Cause:
The resource could not be updated.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-04505
resource {0} cannot be created

Category:
Data

Cause:
The specified name has already been assigned to another resource.

Action:
Specify a unique name, and retry the operation.

WSM-04506
cannot create resource {0}

Category:
Data

Cause:
The resource could not be saved to the data store.

Action:
Retry the operation.

WSM-04507
cannot delete resource {0}

Category:
Data

Cause:
The resource could not be deleted from the data store.

Action:
Retry the operation.

WSM-04508
cannot update resource {0}

Category:
Data

Cause:
The resource could not be updated to the data store.

Action:
Retry the operation.

WSM-04509
cannot initialize the connection to the data store

Category:
Data

Cause:
Connecting to the data store failed.

Action:
Check the data store credentials, and retry the operation. Ensure that WSM-PM is installed, deployed correctly and running at http://<host:port>/wsm-pm/ and by clicking the Validator link. Also, ensure that the database to which WSM-PM connects is up and the mds-owsm data source is configured properly and targeted to the right server.

WSM-04510
The version {0} for resource {1} cannot be found.

Category:
Data

Cause:
The requested version for the specified resource was not found.

Action:
Check the search criteria, and retry the operation.

WSM-04511
cannot perform simultaneous deletes

Category:
Data

Cause:
Deleting multiple resources simultaneously from the data store failed.

Action:
Check supplied data, and retry the operation.

WSM-04512
internal data store error

Category:
Data

Cause:
A generic data store exception occurred.

Action:
Check the data store credentials that were provided and retry the operation. If the problem persists, contact Oracle Support Services.

WSM-04513
cannot commit changes to the repository

Category:
Data

Cause:
A failure occurred while finalizing changes to the data store.

Action:
Retry the operation.

WSM-04514
The version {0} for resource {1} cannot be deleted.

Category:
Data

Cause:
Deleting the specified version(s) of the resource failed.

Action:
Check the supplied values, and retry the operation.

WSM-04515
Auditing is disabled for MDS operations.

Category:
Data

Cause:
An internal error occurred; failed to initialize the auditor.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-04516
The version of the passed resource is invalid.

Category:
Programmatic

Cause:
The requested version of the resource was invalid.

Action:
The version number must be a positive integer.

WSM-04517
cannot update resource {0}

Category:
Programmatic

Cause:
The resource to be updated was concurrently being updated by another process.

Action:
Make sure no other process is attempting to change the resource being updated, and retry the operation.

WSM-04518
document name is invalid

Category:
Programmatic

Cause:
The document name was invalid.

Action:
Specify a name for the document that follows the document naming conventions. Refer to Oracle documentation for the naming rules.

WSM-04519
Unable to create document.

Category:
Programmatic

Cause:
The repository permissions were read-only. Creation of a new document requires write permissions.

Action:
Reconfigure the repository to have write permissions.

WSM-04520
The repository timestamp is invalid.

Category:
Programmatic

Cause:
The repository timestamp was invalid or missing.

Action:
Retry the operation. If the problem persists, consult the diagnostic logs.

WSM-04521
Resource to be deleted does not exist in datastore.

Category:
Data

Cause:
The resource could not be deleted since it does not exist in the data store.

Action:
You don't need to take any action, the resource is not present in the datastore.

WSM-04601
A JDBC URL is required to connect to a database-based MDS repository.

Category:
Programmatic

Cause:
A null or empty JDBC URL was provided when attempting to create an MDS instance for a database-based repository.

Action:
Provide a valid JDBC URL and try again.

WSM-04602
A password is required to connect to a database-based MDS repository.

Category:
Programmatic

Cause:
A null or empty password was provided when attempting to create an MDS instance for a database-based repository.

Action:
Provide a valid password and try again.

WSM-04603
A username is required to connect to a database-based MDS repository.

Category:
Programmatic

Cause:
A null or empty username was provided when attempting to create an MDS instance for a database-based repository.

Action:
Provide a valid username and try again.

WSM-04606
One or more directories are required to connect to a file-based MDS repository.

Category:
Programmatic

Cause:
A path was not provided when attempting to create an MDS instance for a file-based repository.

Action:
Provide a valid directory and try again.

WSM-04611
An MDS session cannot be created due to underlying error "{0}".

Category:
Data

Cause:
MDS encountered an unexpected condition.

Action:
Follow the recommendations for the underlying exception.

WSM-04641
The operation "{0}" for document "{1}" cannot be performed on a closed session.

Category:
Programmatic

Cause:
A operation was requested on a session that has already been closed.

Action:
Create a new repository session and perform the operation again.

WSM-04642
The operation "{0}" for document "{1}" cannot be performed on a read-only session.

Category:
Configuration

Cause:
A write operation was requested on a read-only session. See error message.

Action:
Provide the name of a creator to associate with write operations. Create a new session on a writable repository and try again.

WSM-04643
The operation "{0}" cannot be performed on virtual document "{1}".

Category:
Configuration

Cause:
A write operation was requested on a virtual document.

Action:
Choose a different document name and try again.

WSM-04651
The search criterion "{0}" does not identify a specific document to be created.

Category:
Programmatic

Cause:
The supplied criterion does not have the correct type.

Action:
Supply a NAME search criterion.

WSM-04652
The document "{0}" already exists in the repository.

Category:
Data

Cause:
The document already exists in the repository.

Action:
Choose a different name for the document to create or perform an update instead.

WSM-04653
The document "{0}" cannot be created in a read-only repository.

Category:
Configuration

Cause:
The repository is read-only.

Action:
Reconfigure the repository to support writes and try again.

WSM-04654
The name "{0}" is invalid for creating a document due to underlying reason "{2}".

Category:
Data

Cause:
The document name is invalid for the repository.

Action:
Choose a valid name and try again.

WSM-04655
Repository information cannot be marshalled due to underlying parser error "{2}"

Category:
Other

Cause:
The system does not support the required DOM document builder configuration.

Action:
Correct underlying error or contact Oracle Support Services for assistance.

WSM-04656
Repository information cannot be marshalled due to underlying marshalling error "{2}"

Category:
Data

Cause:
The repository information object could not be marshalled into a DOM document.

Action:
Correct underlying error or contact Oracle Support Services for assistance.

WSM-04657
The document "{0}" cannot be created in a session spanning multiple stores due to underlying error "{2}".

Category:
Configuration

Cause:
The document to be created belongs in a store that is different from other write operations in the session.

Action:
Create the document in a different session.

WSM-04661
The document "{0}" cannot be deleted in a read-only repository.

Category:
Data

Cause:
The repository is read-only.

Action:
Reconfigure the repository to support writes and try again.

WSM-04662
The name "{0}" is invalid for deleting a document due to underlying reason "{2}".

Category:
Data

Cause:
The document name is invalid for the repository.

Action:
Choose a valid name and try again.

WSM-04663
The document "{0}" cannot be deleted in a session spanning multiple stores due to underlying error "{2}".

Category:
Data

Cause:
The document to be created belongs in a store that is different from other write operations in the session.

Action:
Delete the document in a different session.

WSM-04664
Version {1} to {3} of document "{0}" cannot be deleted.

Category:
Data

Cause:
The repository does not support deletion of individual versions of a document.

Action:
Ignore the document version or delete the entire document.

WSM-04671
A concurrent write prevented the document "{0}" from being written due to underlying error "{2}".

Category:
Data

Cause:
Two or more incompatible operations were performed on the same document. A document in this session was modified by another session.

Action:
Perform the incompatible operations in different sessions. Retry the operation.

WSM-04672
The document "{0}" cannot be written to repository due to underlying error "{2}".

Category:
Data

Cause:
An I/O error occurred while writing to repository.

Action:
Correct the underlying problem and retry.

WSM-04673
The session cannot be committed due to underlying error "{2}".

Category:
Data

Cause:
The resource could not be deleted since it does not exist in the data store.

Action:
You don't need to take any action, the resource is not present in the datastore.

WSM-04674
The document "{0}" cannot be validated due to underlying error "{2}".

Category:
Data

Cause:
Validation failed for a metadata object written in the session.

Action:
Correct the underlying problem and retry.

WSM-04681
The document "{0}" to be modified was not found in the repository due to underlying error "{2}".

Category:
Data

Cause:
The document was not found in the repository.

Action:
Create the document instead of modifying it.

WSM-04682
The document "{0}" cannot be modified in a session spanning multiple stores due to underlying error "{2}".

Category:
Data

Cause:
The document to be modified belongs in a store that is different from other write operations in the session.

Action:
Modify the document in a different session.

WSM-04691
The document "{0}" cannot be found in repository due to underlying error "{2}".

Category:
Data

Cause:
The document was not found in the repository.

Action:
Create the document and try again.

WSM-04692
The name "{0}" is invalid for retrieving a document due to the error "{2}".

Category:
Data

Cause:
The document name is invalid for the repository.

Action:
Choose a valid name and try again.

WSM-04693
Version information is not available for document "{0}".

Category:
Data

Cause:
The document does not exist The repository does not support versioning.

Action:
Create the document first. Configure the repository to support versioning.

WSM-04694
An invalid directory was provided to connect to a file-base MDS repository.

Category:
Programmatic

Cause:
An invalid directory was provided when attempting to create an MDS instance for a file-based repository.

Action:
Provide a valid directory and try again.

WSM-04695
The retrieved version of document "{0}" is no longer available.

Category:
Data

Cause:
A new version of the document was created after it was initially retrieved.

Action:
Retry the operation to get the latest version of the document.

WSM-04696
The operation "{0}" cannot be performed on a closed session.

Category:
Programmatic

Cause:
A operation was requested on a session that has already been closed.

Action:
Create a new repository session and perform the operation again.

WSM-04697
The operation "{0}" cannot be performed on a read-only session.

Category:
Configuration

Cause:
A write operation was requested on a read-only session. See error message.

Action:
Provide the name of a creator to associate with write operations. Create a new session on a writable repository and try again.

WSM-04698
Versions {1} to {3} of document "{0}" cannot be deleted due to underlying error "{2}".

Category:
Data

Cause:
An I/O error occurred while trying to delete versions of a document from repository.

Action:
Correct the underlying problem and retry.

WSM-04699
A write lock is not available to delete versions {1} to {3} of document "{0}" due to underlying error "{2}".

Category:
Data

Cause:
A write lock could not be obtained to delete versions of a document.

Action:
Retry the operation.

WSM-04700
cannot delete read-only resources {0}

Category:
Programmatic

Cause:
The document is read-only and cannot be deleted.

Action:
Choose document(s) that are not read-only for modification.

WSM-04701
A connection provider is required to connect to a database-based MDS repository.

Category:
Programmatic

Cause:
A null connection provider was provided when attempting to create an MDS instance for a database-based repository.

Action:
Provide a valid connection provider and try again.

WSM-04702
Timestamp information cannot be marshalled due to underlying parser error "{2}"

Category:
Data

Cause:
The timestamp information object could not be marshalled into a DOM document.

Action:
Retry the operation and if problem persists, contact Oracle Support Services for assistance.

WSM-04703
Repository timestamp information cannot be marshalled due to underlying parser error "{2}"

Category:
Other

Cause:
The system does not support the required DOM document builder configuration.

Action:
Correct underlying error or contact Oracle Support Services for assistance.

WSM-06001
Error obtaining Policy Set.

Category:
Configuration

Cause:
Failed to get PolicySet.

Action:
Check log file for possible causes.

WSM-06017
Error converting to the canonical path for the File Policy Resolver.

Category:
Files

Cause:
An invalid canonical path was passed for the File Policy Resolver.

Action:
Verify the canonical path passed for the File Policy Resolver and retry the operation.

WSM-06036
The class cannot be instantiated.

Category:
Configuration

Cause:
The system could not instantiate a class.

Action:
Consult the Java documentation or Oracle Support Services.

WSM-06101
The policy set cannot be created for null Service Component Architecture (SCA) node.

Category:
Compliance

Cause:
The PolicySet could not be generated for the null Service Component Architecture (SCA) node.

Action:
Pass a valid SCA node object.

WSM-06102
The policy reference URI "{0}" is not valid.

Category:
Compliance

Cause:
The Policy Reference URI provided was not valid.

Action:
Verify that the Policy Reference URI in the SCA node is correct and the policy exists in the repository.

WSM-06103
No configuration has been specified for the Policy Accessor.

Category:
Configuration

Cause:
The Policy Accessor object could not be initialized because it is not correctly configured.

Action:
Call the init method to initialize the Policy Accessor object before invoking this method.

WSM-06104
The protocol specified for Policy Accessor is not supported.

Category:
Compliance

Cause:
A policy access protocol was specified that was invalid for this environment.

Action:
Change protocol to one that is supported by the environment. For J2EE environments, the supported protocols are "local" and "remote"; for J2SE environments, the supported protocols are "classpath", "local", and "remote".

WSM-06105
The duplicate policy references are found in the same Service Component Architecture (SCA) binding node.

Category:
Compliance

Cause:
The same policy has been attached multiple times and so duplicate policy references were found in the same Service Component Architecture (SCA) binding node.

Action:
Remove the duplicate policy references from the SCA binding node by attaching each policy only once.

WSM-06106
The policy reference URI cannot be empty.

Category:
Compliance

Cause:
Empty policy references were found in the Service Component Architecture (SCA) node.

Action:
Verify the Service Component Architecture (SCA) node and make sure the policy references specify a valid value and the referenced policies exist in the repository.

WSM-06107
The node that is expected is <binding.ws> or <component>. The node {0} passed is not a supported node.

Category:
Compliance

Cause:
An unsupported Service Component Architecture (SCA) node was found.

Action:
Specify a supported SCA node. Consult Oracle documentation for further details

WSM-06108
Error initializing the Oracle WSM Policy Resolver because incorrect configuration is passed

Category:
Configuration

Cause:
The Policy Resolver did not get created. This could be due to the wrong configuration being passed.

Action:
Verify the configuration passed for creating the Policy Resolver. Verify that the correct Policy Accessor protocol is passed.

WSM-06109
Cannot retrieve policies.

Category:
Data

Cause:
The policies were not retrieved. This may be due to incorrect policy references in the Service Component Architecture (SCA) node.

Action:
Verify that the policy references are referring to policies that exist in the repository. Also, ensure that the data store is seeded with policies.

WSM-06110
The MetaData Store (MDS) home cannot be null.

Category:
Configuration

Cause:
The Policy Repository was not valid because MDS Home is set to null.

Action:
Check the mds.home.module property for the correct value for MDS Home.

WSM-06111
The policy name cannot be null.

Category:
Compliance

Cause:
The policy name passed was null or empty.

Action:
Verify that the policy name is not an empty string, and verify that a null policy name is not being passed.

WSM-06112
Policies are not supported for a node of type:{0}.

Category:
Compliance

Cause:
Policies cannot be retrieved for unsupported Service Component Architecture (SCA) nodes.

Action:
Verify that a supported SCA node is provided for retrieving the policy.

WSM-06113
The configuration name cannot be null or empty.

Category:
Configuration

Cause:
The configuration file was either empty or did not exist.

Action:
Verify that the configuration file exists and contains policy references to retrieve policies from the Policy Repository.

WSM-06114
The home directory for the File Policy Resolver cannot be null.

Category:
Files

Cause:
The home directory for File Policy Resolver was null.

Action:
Verify that a valid home directory is passed for the File Policy Resolver.

WSM-06115
The path for the File Policy Resolver does not exist.

Category:
Files

Cause:
The path for File Policy Resolver did not exist.

Action:
Ensure that a valid path is passed for File Policy Resolver.

WSM-06116
The path for the File Policy Resolver is not a directory.

Category:
Files

Cause:
An invalid directory name was passed for the File Policy Resolver.

Action:
Verify that a valid directory name is passed for the File Policy Resolver.

WSM-06118
The resource name for the File Policy Resolver cannot be null.

Category:
Files

Cause:
The resource name for the File Policy Resolver is null.

Action:
Verify that a valid resource name is passed for the File Policy Resolver.

WSM-06119
The file {0} for the File Policy Resolver does not exist under {1}.

Category:
Files

Cause:
The file did not exist.

Action:
Verify that the file exists at the specified location.

WSM-06120
The resource name for the File Policy Resolver cannot be null.

Category:
Files

Cause:
The resource name for the File Policy Resolver was null.

Action:
Ensure that a non-null resource name is passed for the File Policy Resolver.

WSM-06121
No policy is found for the policy reference: {0}.

Category:
Data

Cause:
No policy was found for the specified policy reference.

Action:
Verify that the policy exists in the repository for the given policy reference, and that the correct policy reference is passed.

WSM-06122
Error retrieving policies.

Category:
Data

Cause:
An unexpected error occurred while retrieving the policies from the Policy Manager.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-06123
Error initializing internally the File Policy Resolver: {0} {1}

Category:
Security

Cause:
An unexpected error occurred while initializing the File Policy Resolver.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-06124
Error initializing the Oracle WSM Policy Manager Policy Resolver : {0} {1}.

Category:
Configuration

Cause:
An unexpected error occurred while initializing the Policy Manager Policy Resolver. The Policy Manager Policy Resolver was not able to find the property named mds.config

Action:
Verify that the property mds.config exists and is referencing a valid property file.

WSM-06125
Error in the XPath expression {0}.

Category:
Compliance

Cause:
The XPath Expression for the policy reference for the given Service Component Architecture (SCA) node was invalid.

Action:
Verify the XPath for the policy reference within the SCA node.

WSM-06128
Error accessing the PolicySet : {0} : {1}.

Category:
Configuration

Cause:
An unexpected error occurred while accessing the PolicySet.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-06129
Error parsing the PolicySet : {0} : {1}.

Category:
Configuration

Cause:
An unexpected error occurred while parsing the PolicySet.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-06130
Error creating the policy parser.

Category:
Configuration

Cause:
The Policy Parser did not get created.

Action:
Check the configuration for the Policy Parser.

WSM-06132
Error creating a connection to Oracle WSM Policy Manager.

Category:
Configuration

Cause:
A failure occurred while connecting to the Policy Manager.

Action:
Ensure that the Policy Manager is up and running. Ensure that WSM-PM is installed, deployed correctly and running at http://<host:port>/wsm-pm/ and by clicking the Validator link. Also, ensure that the database to which WSM-PM connects is up and the mds-owsm data source is configured properly and targeted to the right server.

WSM-06133
Error connecting to Oracle WSM Policy Manager.

Category:
Configuration

Cause:
A failure occurred while connecting to Policy Manager J2EE Application.

Action:
Before connecting to a Policy Manager, ensure that the Policy Manager is up and running.

WSM-06134
The class cannot be found.

Category:
Configuration

Cause:
The class could not be found in the classpath.

Action:
Verify that the class name is correct in the configuration files and ensure that the class is specified in the classpath variable.

WSM-06135
The class cannot be loaded due to Java 2 security restrictions.

Category:
Configuration

Cause:
Some classes were not loaded due to class loading security restrictions.

Action:
Contact the site administrator or Java documentation to ensure that the classes have the necessary Java2 security permissions.

WSM-06137
The "mds" policy access protocol is deprecated - use "local" instead.

Category:
Configuration

Cause:
A deprecated Policy Accessor Protocol was specified.

Action:
Update the configuration to use the standard protocol name.

WSM-06138
The "owsm" policy access protocol is deprecated - use "remote" instead.

Category:
Configuration

Cause:
A deprecated Policy Accessor protocol was specified.

Action:
Update the configuration to use the standard protocol name.

WSM-06139
Error closing a stream

Category:
Configuration

Cause:
Failure occurred in closing the stream while parsing the configuration file or the policy in the FILE protocol.

Action:
Verify that the correct configuration file or policy name is provided.

WSM-06140
Failure finding policy {0} in the classpath roots path {1}.

Category:
Configuration

Cause:
The policy did not exist in any of the configured roots. The configured roots are invalid.

Action:
Correct the reference to point to a policy that exists. Correct the classpath roots to point to the correct locations.

WSM-06141
Error initializing Policy Resolver.

Category:
Configuration

Cause:
The Policy Resolver was not initialized.

Action:
Invoke the init method to initialize the Policy Resolver before executing this method.

WSM-06142
Unable to retrieve policy store timestamp.

Category:
Configuration

Cause:
The Policy Resolver could not connect to Policy Manager to retrieve the policy store timestamp.

Action:
Check the MDS configuration file.

WSM-06143
The validation check in the policy "{0}" failed.

Category:
Configuration

Cause:
An error occurred while validating the policy.

Action:
Ensure that the policy is valid.

WSM-06144
Null policy subject value is not allowed from JEE application.

Category:
Compliance

Cause:
The null policy subject value was passed from JEE application.

Action:
Ensure that a valid policy subject is passed from the JEE application.

WSM-06145
Internal system error, cannot look up credential

Category:
Configuration

Cause:
Failure occurred while looking up credentials.

Action:
Internal system configuration error. Contact Oracle Support Services.

WSM-06146
Error deleting the attachment entries.

Category:
Configuration

Cause:
Failure occurred while deleting the attachment entries.

Action:
Ensure that a valid list of policy subjects for deactivated lifecycle type is passed

WSM-06147
There is mismatch in Policy reference category "{0}" and Policy category "{1}". Policy reference category should match with Policy category.

Category:
Data

Cause:
Mismatch in expected policy category and fetched policy category.

Action:
Confirm that the Policy Reference category is correct and that it matches the Policy category.

WSM-06148
Unable to apply property overrides to Policy

Category:
Data

Cause:
Unable to apply property overrides to Policy.

Action:
Make sure the policy model conforms to the Oracle Web service policy model.

WSM-06149
The policy reference URI is not valid : {0}

Category:
Compliance

Cause:
The Policy Reference URI provided was not valid.

Action:
Verify that the Policy Reference URI is correct.

WSM-06150
Invalid category : {0} for policy : {1}. Only policies assigned to the security category are supported.

Category:
Compliance

Cause:
The Policy category provided was not valid.

Action:
Verify that the Policy category is correct.

WSM-06152
The Policy Cache is not available.

Category:
Compliance

Cause:
The Policy Cache is not available.

Action:
You may need to restart the server.

WSM-06153
Could not access the Policy Cache.

Category:
Compliance

Cause:
Cannot access the Policy Cache.

Action:
You may need to restart the server.

WSM-06154
Could not initialize Policy Java Object Cache.

Category:
Compliance

Cause:
Cannot initialize the Policy Cache.

Action:
You may need to restart the server.

WSM-06155
Could not re-create Policy Java Object Cache.

Category:
Compliance

Cause:
Could not re-create the Policy Cache.

Action:
You may need to restart the server.

WSM-06156
The policy referenced by URI "{0}" could not be retrieved since the URI is invalid.

Category:
Compliance

Cause:
The policy URI is missing, empty or contains invalid characters.

Action:
Provide a valid URI for a policy in the repository or remove the reference.

WSM-06157
The policy referenced by URI "{0}" could not be retrieved due to incorrect repository configuration.

Category:
Compliance

Cause:
The repository database is not configured correctly or not running.

Action:
Verify that the repository database is configured correctly according to the user documentation and is running.

WSM-06158
The policy referenced by URI "{0}" does not exist in the repository.

Category:
Data

Cause:
The referenced policy does not exist in the repository.

Action:
Provide the URI for a policy in the repository or load the desired policy into the repository.

WSM-06159
The policy referenced by URI "{0}" could not be retrieved due to invalid credential "{1}" being used to connect to the Policy Manager.

Category:
Compliance

Cause:
Cannot connect to the policy manager due to credential issue.

Action:
Verify that credentials are correctly specified, if not using the default principal, and that the principal is authorized to access the policy manager application.

WSM-06160
The policy referenced by URI "{0}" could not be retrieved since Policy Manager is either not deployed or not in active state.

Category:
Compliance

Cause:
The policy manager application has not been deployed or is not running.

Action:
Verify that the policy manager application is deployed and configured correctly and in an active state.

WSM-06161
The policy referenced by URI "{0}" could not be retrieved since Policy Manager is not deployed.

Category:
Compliance

Cause:
The policy manager application has not been deployed.

Action:
Verify that the policy manager application is deployed.

WSM-06162
The policy referenced by URI "{0}" could not be retrieved as connection to Policy Manager cannot be established at "{1}" due to invalid configuration or inactive state.

Category:
Compliance

Cause:
The policy manager application is not running or is not configured correctly.

Action:
Verify that the policy manager application is configured correctly and is in an active state. Provide correct configuration for URL of policy manager, setting its listen address if using auto-discovery, and ensure that any required SSL certificate is valid.

WSM-06163
The policy referenced by URI "{0}" could not be retrieved as connection to Policy Manager cannot be established due to invalid certificate configuration.

Category:
Compliance

Cause:
Cannot connect to the policy manager due to certificate issue.

Action:
Verify that credential store and trust store location are correctly specified, and ensure that the certificate entry is valid.

WSM-06201
The {0} repository accessor class cannot be accessed due to underlying error "{1}".

Category:
Configuration

Cause:
The nullary constructor for the specified accessor is not accessible to the configuration framework.

Action:
Specify a valid accessor.

WSM-06202
The {0} repository accessor class cannot be initialized due to underlying error "{1}".

Category:
Configuration

Cause:
A exception was encountered during evaluation of a static initializer for the specified accessor class.

Action:
Specify a valid accessor.

WSM-06203
The {0} repository accessor class cannot be used as a repository accessor because it does not implement the {1} interface.

Category:
Configuration

Cause:
The specified accessor does not implement the IRepositoryAccessor interface.

Action:
Specify a valid accessor.

WSM-06204
The {0} repository accessor class cannot be linked due to underlying error "{1}".

Category:
Configuration

Cause:
The specified accessor depends on a class whose signature has changed since the accessor was compiled.

Action:
Update the accessor class or revert to an older version of the dependent class.

WSM-06205
The repository accessor "{0}" cannot be found due to underlying error "{1}".

Category:
Configuration

Cause:
The specified accessor was not found.

Action:
Specify a valid accessor.

WSM-06206
The {0} repository accessor class cannot be instantiated due to underlying error "{1}".

Category:
Configuration

Cause:
The specified accessor is an abstract class, an interface, an array class, a primitive type, or void, or the class does not have a nullary constructor.

Action:
Specify a valid accessor.

WSM-06207
A task scheduler was not available for configuring the {0} repository accessor for context "{1}".

Category:
Configuration

Cause:
A task scheduler was not supplied to the configuration framework.

Action:
Provide a task scheduler to the configuration framework.

WSM-06208
Access to the {0} repository accessor class is denied due to underlying error "{1}".

Category:
Configuration

Cause:
The configuration framework does not have permission to instantiate the specified accessor.

Action:
Ensure the necessary permissions are granted to the WSM code base.

WSM-06214
A task scheduler was provided for configuring the {0} repository accessor for context "{1}".

Category:
Configuration

Cause:
A task scheduler was supplied to the configuration framework.

Action:
None.

WSM-06219
A task scheduler was not available for configuring the {0} repository accessor for the default context.

Category:
Configuration

Cause:
A task scheduler was not supplied to the configuration framework.

Action:
Provide a task scheduler to the configuration framework.

WSM-06220
A task scheduler was provided for configuring the {0} repository accessor for the default context.

Category:
Configuration

Cause:
A task scheduler was supplied to the configuration framework.

Action:
None.

WSM-06221
The password credentials cannot be obtained from the Credential Store.

Category:
Configuration

Cause:
Failure occurred while querying for credentials from CSF.

Action:
Check CSF configuration.

WSM-06222
The credentials passed to the credentials store are expired.

Category:
Configuration

Cause:
The Credentials have expired.

Action:
Ensure valid credentials are passed

WSM-06223
The access to the store or credentials is denied.

Category:
Configuration

Cause:
The requested access Credentials or Store is denied.

Action:
Ensure Store is properly initialized and valid credentials are passed

WSM-06224
Unexpected exception "{0}" caught when privileged method is called.

Category:
Configuration

Cause:
Unexpected exception caught on calling a privileged code.

Action:
Check the underlying signature of method called in privileged code

WSM-06225
Unable to retrieve credentials for the specified CSF key {0}.

Category:
Configuration

Cause:
Credential configuration in the policy accessor configuration file was incorrect.

Action:
Configure policy with valid CSF key.

WSM-06226
An instance of the {0} bean was obtained for accessing the local repository at path "{1}".

Category:
Configuration

Cause:
A bean instance was obtained by the configuration framework.

Action:
None.

WSM-06227
An instance of the {0} bean was obtained for accessing the remote repository.

Category:
Configuration

Cause:
A bean instance was obtained by the configuration framework.

Action:
None.

WSM-06228
Unable to retrieve "ENTERPRISE" model via classpath accessor during configuration initialization.

Category:
Configuration

Cause:
The seed ENTERPRISE model cannot be retrieved via ClasspathAccessor during configuration manager startup.

Action:
Verify the availability of seed documents jar witin the classpath.

WSM-06229
Unable to retrieve "default" resource via classpath accessor during configuration initialization.

Category:
Configuration

Cause:
The seed default resource cannot be retrieved via ClasspathAccessor during configuration manager startup.

Action:
Verify the availability of seed documents jar witin the classpath.

WSM-06301
Subject Metadata is required when registering a listener.

Category:
Programmatic

Cause:
A null value was provided for the subject metadata.

Action:
Provide a valid metadata.

WSM-06302
A listener is required for asynchronous notification.

Category:
Programmatic

Cause:
A null value was provided for asynchronous listener registration.

Action:
Provide a valid listener.

WSM-06303
The method "{0}" was not called with required permission "{1}"

Category:
Security

Cause:
The method was not called with required permission

Action:
Ensure necessary permissions are granted to the caller before calling the required methods.

WSM-06401
The assembly referenced by "{0}" is not registered with the application.

Category:
Programmatic

Cause:
The assembly is not registered with the application.

Action:
Retry the operation after registering the assembly with the application.

WSM-06402
The resource pattern identifying the metadata model is not provided.

Category:
Programmatic

Cause:
The resource pattern identifying the metadata is not provided.

Action:
Ensure that a valid resource pattern is passed for identifying the metadata.

WSM-06403
Valid instance of StorageProvider must be provided for accessing the assembly file.

Category:
Programmatic

Cause:
A storage provider is required for extracting metadata information from assembly file.

Action:
Retry the operation with valid instance of storage provider.

WSM-06404
The resource pattern "{0}" identify the subject is invalid or incomplete .

Category:
Programmatic

Cause:
The resource pattern identifying the subject is invalid.

Action:
Retry the operation with valid value for subject resource pattern.

WSM-06405
The subject referenced by "{0}" is not registered with the assembly.

Category:
Programmatic

Cause:
The subject is not registered with the assembly.

Action:
Retry the operation after registering the subject with the assembly.

WSM-06406
Valid PolicySubjectDefinition must be provided for retrieving the effective policy set.

Category:
Programmatic

Cause:
The subject definition is not provided for creating policy set.

Action:
Provide valid value for subject definition for creating policy set.

WSM-06407
Attempted to register the listener "{0}" to a policy subject "{1}" which was already previously registered with listener "{2}".

Category:
Programmatic

Cause:
Attempt to reregistering a listener for a policy subject.

Action:
Make sure that a policy subject registers a listener only once.

WSM-06408
The local policy attachment data for policy subject "{0}" is not available due to underlying IO exception "{1}".

Category:
Data

Cause:
The policy assembly containing the policy subject's metadata cannot be accessed.

Action:
Correct the underlying condition and retry the operation.

WSM-06409
The local policy attachment data for policy subject "{0}" is not available due to underlying JAXB exception "{1}".

Category:
Data

Cause:
The policy assembly containing the policy subject's metadata is corrupt.

Action:
Correct the underlying condition and retry the operation.

WSM-06410
JMX APIs are not available in this environment, verify environment configuration for JMX.

Category:
Data

Cause:
JMX api's are not available in this environment, so not initializing PolicyApplicationMBean

Action:
Verify environment configuration for JMX.

WSM-06411
A task scheduler was not available for configuring the repository accessor due to undelying error "{0}".

Category:
Configuration

Cause:
OWSM Configuration Manager not able to set the task scheduler.

Action:
Provide a task scheduler to the configuration framework.

WSM-06412
The partition aware scheduler fetch failed due to underlying Naming exception "{0}".

Category:
Data

Cause:
The partition aware scheduler cannot be fetched.

Action:
Correct the underlying condition and retry the operation.

WSM-06413
The value of term "{0}" from resource pattern terms "{1}" is not provided and cannot be resolved by platform support API either, hence will be set to default "{2}", please verify the cause.

Category:
Data

Cause:
PlatformSupport API returned unexpected null value in J2EE environment.

Action:
Check the log for more info and possible cause.

WSM-07501
Failure in Oracle WSM Agent processRequest, category={0}, function={1}, application={2}, composite={3}, modelObj={4}, policy={5}, policyVersion={6}, assertionName={7}.

Category:
Configuration

Cause:
Processing request failed in the security interceptor while enforcing policy.

Action:
Check the log file for possible causes.

WSM-07502
Failure in Oracle WSM Agent processResponse, category= {0}, function={1}, application={2}, composite={3}, modelObj={4}, policy={5}, policyVersion={6}, assertionName={7}.

Category:
Configuration

Cause:
Processing response failed in the security interceptor while enforcing policy.

Action:
Check the log file for possible causes.

WSM-07503
Failure in Oracle WSM Agent processFault, category= {0}, function={1}, application={2}, composite={3}, modelObj={4}, policy={5}, policyVersion={6}, assertionName={7}.

Category:
Configuration

Cause:
Processing fault failed in the security interceptor while enforcing policy.

Action:
Check the log file for possible causes.

WSM-07504
Failure in Oracle WSM Agent processEvent, category= {0}, function={1}, application={2}, composite={3}, modelObj={4}.

Category:
Configuration

Cause:
Processing Fabric Lifecycle event failed in security interceptor.

Action:
Check the log file for possible causes

WSM-07505
Failure in Oracle WSM Agent initialization, category= {0}, function={1}.

Category:
Configuration

Cause:
Agent initialization failed in the security interceptor.

Action:
Check the log file for possible causes.

WSM-07506
Failure in Oracle WSM Agent processFinish, category= {0}, function={1}, application={2}, composite={3}, modelObj={4}.

Category:
Configuration

Cause:
Agent finish failed in the security interceptor.

Action:
Check the log file for possible causes.

WSM-07507
Failure in Oracle WSM Agent, category= {0}, function={1}, stage={2} due to RuntimeException.

Category:
Data

Cause:
An unexpected RuntimeException was encountered while trying to access security interceptor.

Action:
Check the log file for possible causes and retry the operation.

WSM-07508
Oracle WSM Agent initialization failed due to PolicySet validation errors: {0}, with PolicySet={1}

Category:
Configuration

Cause:
Agent not initialized due to PolicySet validation errors

Action:
Check the log for detail

WSM-07509
Oracle WSM Agent must be initialized with valid properties. Following parameters [{0}] are either Empty or null

Category:
Configuration

Cause:
Agent not initialized with valid parameters.

Action:
Initialize the Agent with required parameters

WSM-07510
JAX-RS Filter is already initialized for policy subject with Resource Pattern "{0}". It can not be passed another PolicySubjectDefintion with Resource Patter "{1}". {2}

Category:
Data

Cause:
The JAX-RS Filter was already initialized with a PolicySubjectDefinition. It can not be passed any more PolicySubjectDefinition objects.

Action:
Do not Initialize the JAX-RS Filter multiple times.

WSM-07511
Failed to initialize JAX-RS Filter. The PolicySubjectDefinition array is either null, empty or has length > 1

Category:
Data

Cause:
JAX-RS Filter not initialized with an array of PolicySubjectDefinition objects whose length is exactly 1. The filter supports a single PolicySubjectDefinition at any time.

Action:
Create a PolicySubjectDefinition array with a single object and retry the operation.

WSM-07512
PolicySubjectDefinition could not be created for the JAX-RS resource. The JAX-RS resource object passed to create PolicySubjectDefinition was null.

Category:
Programmatic

Cause:
PolicySubjectDefinition could not be created for the JAX-RS resource. The JAX-RS resource object passed to create PolicySubjectDefinition was null.

Action:
Pass a valid, non-null resource class object.

WSM-07513
A resource filter could not be created for the JAX-RS resource. Either the HttpServletRequest [{0}] or the HttpServletResponse [{1}] passed to the constructor was null.

Category:
Programmatic

Cause:
RESTResourceFilter could not be instantiated. Either of the servlet request or response objects passed by the RESTResourceFilterFactory was null.

Action:
Make sure the HttpServletRequest/Response objects were injected in the filter factory.

WSM-07514
OWSM Security Filter failed to initialize. The param-value of "oracle.wsm.metadata.policySet" init-param can not be parsed.

Category:
Configuration

Cause:
The XML value configured as CDATA for "oracle.wsm.metadata.policySet" init-param in the application's web.xml was not parsed successfully.

Action:
Make sure that the value of "oracle.wsm.metadata.policySet" init-param is well-formed XML enclosed as CDATA.

WSM-07515
OWSM Security Filter failed to initialize. The filter was unable to create a valid ResourcePattern object for this servlet: {0}.

Category:
Configuration

Cause:
The servlet may be under the default (root) context path.

Action:
Make sure that the servlet to be protected is not under the default (root) context path.

WSM-07516
OWSM Authorization Code Client Filter failed to initialize. The param-value of "oracle.wsm.metadata.policySet" init-param can not be parsed.

Category:
Configuration

Cause:
The XML value configured as CDATA for "oracle.wsm.metadata.policySet" init-param in the application's web.xml was not parsed successfully.

Action:
Make sure that the value of "oracle.wsm.metadata.policySet" init-param is well-formed XML enclosed as CDATA.

WSM-07600
Error while copying the message.

Category:
Security

Cause:
An unexpected error occurred while cloning SOAP or normalized message context.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-07601
Failure initializing the WSPolicyExecutor class {0}.

Category:
Configuration

Cause:
An unexpected error occurred while initializing the policy engine.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-07602
Failure in WS-Policy Execution due to exception.

Category:
Security

Cause:
Due to an unexpected error, policy execution failed at runtime.

Action:
Check the log file for possible causes.

WSM-07603
Failure in log assertion execution caused by exception.

Category:
Files

Cause:
File I/O problem or SOAP message access problem occurred.

Action:
Verify file access permission and the SOAP message.

WSM-07604
Internal error during policy enforcement.

Category:
Security

Cause:
An unexpected error occurred while enforcing the policy.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-07605
The binding.ws port ID {0} is invalid.

Category:
Configuration

Cause:
An unexpected error occurred in the Oracle WSM processEvent API.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-07606
Policy {0} execution failure.

Category:
Security

Cause:
Due to an unexpected error, policy execution failed at runtime.

Action:
Check the log file for possible causes.

WSM-07607
Failure in execution of assertion {0} executor class {1}.

Category:
Security

Cause:
The policy engine failed to execute an assertion.

Action:
Check the log file for possible causes.

WSM-07608
The assertion type is not valid.

Category:
Security

Cause:
Policy execution failed due to an invalid assertion.

Action:
Check the assertion type.

WSM-07609
Policy with attachto value of {0} cannot be applied to subject of type {1}.

Category:
Security

Cause:
The attached policy was incompatible with the subject.

Action:
Verify that the subject type and the policy's Attachto value are compatible.

WSM-07610
Internal error in policy status audit. One or more of the argument passed is null, result:{0}, agentFunction:{1}, policy:{2}, msgCtx:{3}

Category:
Configuration

Cause:
An internal error occurred; the enforcement auditor encountered one or more null arguments.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-07611
Failure initializing of enforcement auditor: category={0}, function= {1}, topologyNode={2}.

Category:
Configuration

Cause:
An internal error occurred; the enforcement auditor initialization failed.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-07612
Failure shutting down enforcement auditor.

Category:
Configuration

Cause:
An internal error occurred; the enforcement auditor shutdown failed.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-07613
Failure enforcing auditing policy.

Category:
Configuration

Cause:
An internal error occurred while auditing security or management policy enforcement.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-07614
Failure in Agent initialization due to invalid topology node path. Topology node path cannot be null or empty for non-JSE client. category={0}, function={1}, topologyNode={2}, isRunningInJEE={3}

Category:
Configuration

Cause:
Oracle WSM Agent initialization failed due to problem creating and initializing DMS instrumentation. An invalid, null, or empty topology node path was encountered for non-JSE client.

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-07616
Resource name not retrievable from MessageContext. Guard evaluation requires resource name to be present in MessageContext

Category:
Security

Cause:
Resource name not retrievable from MessageContext. Guard evaluation requires resource name to be present in MessageContext

Action:
Retry the operation. If the problem persists, contact Oracle Support Services.

WSM-07617
Policy: {0} contains unsupported assertions.

Category:
Security

Cause:
Policy contains unsupported assertions. Assertions of type http-security are not supported for WLS JAXWS web services.

Action:
Check the assertion type.

WSM-07618
Failed to execute the assertion "{0}" in the conditional policy. {1}

Category:
Security

Cause:
Failed to execute the assertion

Action:
Check exception stack trace for details

WSM-07619
Failed to retrieve the Weblogic Server subject.

Category:
Security

Cause:
An error occurred while retrieving Weblogic Server subject.

Action:
Check log file for possible cause.

WSM-07620
Agent cannot enforce policies due to either failure in retrieving polices or error in validations, detail= "{0}".

Category:
Security

Cause:
Either policies can not be retrieved or Policy/PolicySet have validation errors.

Action:
Correct the validation errors and retry again.

WSM-07621
Oracle WSM Advertisement Engine failed with valid PolicySet, validation errors: [{0}], and PolicySet: [{1}]

Category:
Other

Cause:
Advertisment failed due to runtime PolicySet validation error in WSMEngineInvoker

Action:
Check log for detail to correct Runtime PolicySet

WSM-07622
The agent instance for enforcement cannot be null for scope "{0}". Check logs for details.

Category:
Data

Cause:
The agent instance for enforcement is null.

Action:
Check server logs for more details.

WSM-09001
The audit event definitions cannot be found.

Category:
Configuration

Cause:
Component audit event definitions were missing.

Action:
Check the installation for any missing or corrupted JAR files.

WSM-09002
The audit event definitions file cannot be opened.

Category:
Configuration

Cause:
Component audit event definitions could not be opened.

Action:
Check the installation for any corrupted JAR files, or free up system resources.

WSM-09003
The audit event definitions file cannot be read.

Category:
Configuration

Cause:
Component's audit event definitions were not readable.

Action:
Check the installation for any corrupted JAR files.

WSM-09004
Component auditing cannot be initialized.

Category:
Logging

Cause:
The audit framework encountered an error.

Action:
Check the logs for the possible causes.

WSM-09005
It is not possible to verify that the event is enabled.

Category:
Logging

Cause:
The audit framework encountered an error.

Action:
Check the logs for the possible causes.

WSM-09006
The event cannot be audited. Another attempt will be made to audit the event.

Category:
Logging

Cause:

Action:

WSM-09007
The event cannot be audited.

Category:
Logging

Cause:
The audit framework encountered an error.

Action:
Check the logs for the possible causes.

WSM-09008
A URL cannot be created for {0}.

Category:
Logging

Cause:
XML utility encountered an error.

Action:
Check the logs for the possible causes.

WSM-09009
Failure parsing the XML file

Category:
Logging

Cause:
XML utility encountered an error.

Action:
Check the logs for the possible causes.

WSM-09010
Error opening and/or closing the stream

Category:
Logging

Cause:
XML utility encountered an error.

Action:
Check the logs for the possible causes.

WSM-09011
Error writing the XML file

Category:
Logging

Cause:
XML utility encountered an error.

Action:
Check the logs for the possible causes.

WSM-09012
Key, {0}, is not found in the resource bundle {1}.

Category:
Configuration

Cause:
No key was found in the provided resource bundle.

Action:
Add the key to the resource bundle and retry the operation.

WSM-09013
Failure shutting down auditing.

Category:
Logging

Cause:
An exception was caught when attempting to shut down the audit framework.

Action:
Examine the stack trace for any underlying errors.

WSM-09014
Streaming SOAP message attachment is not being logged.

Category:
Logging

Cause:
SOAP message attachment was not logged because it was a streaming attachment.

Action:
Check the logs for the possible causes.

WSM-09015
Interrupted while checking out object from pool.

Category:
Other

Cause:
Received interrupt while checking out from pool.

Action:
Check the logs for the possible causes.

WSM-09016
Failure creating transformer using factory {0}.

Category:
Other

Cause:
Transformer factory failed to create new transformer instance.

Action:
Check the logs for the possible causes.

WSM-09017
Failure checking out a transformer instance.

Category:
Other

Cause:
Failure checking out a transformer instance.

Action:
Check the logs for the possible causes.

WSM-09018
A ScheduledExecutorService is required when creating a scheduler wrapper.

Category:
Other

Cause:
A ScheduledExecutorService was not provided when constructing a wrapper.

Action:
Provide a valid ScheduledExecutorService instance.

WSM-09019
An executor requires a task for scheduling.

Category:
Other

Cause:
A task was not provided when scheduling a task.

Action:
Provide a valid task.

WSM-09020
An executor rejected a task due to error "{0}".

Category:
Other

Cause:
The ScheduledExecutorService refused to schedule a task.

Action:
Check the logs for the possible causes.

WSM-09021
A TimerManager is required when creating a scheduler wrapper.

Category:
Other

Cause:
A TimerManager was not provided when constructing a wrapper.

Action:
Provide a valid TimerManager instance.

WSM-09022
A timer cannot schedule a task due to illegal argument error "{0}".

Category:
Other

Cause:
A task was not provided when scheduling a task. The scheduling parameters were negative.

Action:
Provide a valid task. Provide non-negative values.

WSM-09023
A timer cannot schedule a task due to illegal state error "{0}".

Category:
Other

Cause:
A task could not be scheduled because the underlying TimerManager was stopped.

Action:
Schedule the task using a running TimerManager.

WSM-09024
Failure parsing the XML URL when: {0}, from: {1}

Category:
Logging

Cause:
XML utility parseXMLDocument from URL encountered an error.

Action:
Check the logs for the possible causes.

WSM-09025
Unable to initialize WSM Coherence cache service, Defaulting to local Coherence cache. {0}

Category:
Logging

Cause:
Unable to initialize Coherence cache service.

Action:
Make sure that the Coherence is properly configured for the cluster environment.

WSM-09027
Resource bundle {0} is missing.

Category:
Configuration

Cause:
Resource bundle is missing.

Action:
Add the resource bundle and retry the operation.

WSM-09028
Failed to get server log directory due to error {0}.

Category:
Other

Cause:
Failed to get server Log directory.

Action:
See logs for details.

WSM-09029
Diagnostic logging handler creation failed due to error {0}.

Category:
Other

Cause:
Failed to create handler for diagnosis logs.

Action:
See logs for details.